

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12406890
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Kuo; Ming-Sung et al.

Method for measuring overlay shift of bonded wafers

Abstract

A measurement pattern for monitoring overlay shift of bonded wafers includes a top wafer pattern and a bottom wafer pattern. The top wafer pattern includes a first portion with a width $Wx1$ measured along a first axis. The bottom wafer pattern includes a first part with a width $Wx2$ measured along the first axis, wherein the first portion of the top wafer pattern and the first part of the bottom wafer pattern are separated by a target distance Dx , and wherein the measurement pattern satisfies the following measurement formulas: $Tx > Dx - Sx$; $Tx < Dx - Sx + Wx2$; $Tx > Sx$; $Tx < Dx - Sx + Wx1$; wherein, Tx represents a searching distance for finding an end-point of the first portion or an end-point of the first part; and Sx represents an actual shifting amount of the first portion.

Inventors: Kuo; Ming-Sung (Hsinchu, TW), Hsiao; Hsun-Kuo (Hsinchu, TW), Chen; Chung-Cheng (Miaoli County, TW), Chen; Po-Wei (Hsinchu, TW)

Applicant: Taiwan Semiconductor Manufacturing Company, Ltd. (Hsinchu, TW)

Family ID: 82594029

Assignee: Taiwan Semiconductor Manufacturing Company, Ltd. (Hsinchu, TW)

Appl. No.: 18/757511

Filed: June 28, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240347396 A1	Oct. 17, 2024

Related U.S. Application Data

continuation parent-doc US 17395426 20210805 US 12057353 child-doc US 18757511

Publication Classification

Int. Cl.: H01L21/66 (20060101)

U.S. Cl.:

CPC H01L22/12 (20130101); H01L22/26 (20130101);

Field of Classification Search

CPC: H01L (22/12); H01L (22/26); H01L (22/30); H01L (21/681); H01L (21/8221); H01L (21/822)

USPC: 156/64

References Cited

U.S. PATENT DOCUMENTS				
Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
12057353	12/2023	Kuo	N/A	H01L 22/26

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION (1) This application is a continuation application of and claims the priority benefit of U.S. application Ser. No. 17/395,426, filed on Aug. 5, 2021, now allowed. The entirety of the above-mentioned patent application is hereby incorporated by reference herein and made a part of this specification.

BACKGROUND

(1) Improvements for wafer to wafer bonding are increasingly important in 3DIC (three-dimensional integrated circuit) structures. For example, wafer bonding has been used to provide increased integration by forming vertical stacks of semiconductor devices without the need for intervening structures such as substrates or circuit boards. Current semiconductor process for monitoring wafer bonding shift is usually based on the visual inspection from the naked-eye to judge the bonding accuracy. However, the measurement accuracy is rough, and the productivity may be slow. More effective and less time-consuming methods are proposed to improve overlay shifting control.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is noted that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the critical dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.

(2) FIG. 1 is a flow chart of a method for measuring overlay shift of bonded wafers according to some exemplary embodiments of the present disclosure.

(3) FIG. 2A to FIG. 6D are schematic sectional and top-views of various stages of a method for measuring overlay shift of bonded wafers according to some exemplary embodiments of the present disclosure.

(4) FIG. 7 is a schematic top view of one stage in a method for measuring overlay shift of bonded wafers according to some comparative embodiments of the present disclosure.

(5) FIG. 8 is a schematic top view of one stage in a method for measuring overlay shift of bonded wafers according to some comparative embodiments of the present disclosure.

(6) FIG. 9 is a schematic top view of a measurement pattern of bonded wafers according to some exemplary embodiments of the present disclosure.

DETAILED DESCRIPTION

(7) The following disclosure provides many different embodiments, or examples, for implementing different features of the provided subject matter. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a second feature over or on a first feature in the description that follows may include embodiments in which the second and first features are formed in direct contact, and may also include embodiments in which additional features may be formed between the second and first features, such that the second and first features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.

(8) Further, spatially relative terms, such as “beneath”, “below”, “lower”, “on”, “over”, “overlying”, “above”, “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

(9) FIG. 1 is a flow chart of a method for measuring overlay shift of bonded wafers according to some exemplary embodiments of the present disclosure. FIG. 2A to FIG. 6D are schematic sectional and top-views of various stages of a method for measuring overlay shift of bonded wafers according to some exemplary embodiments of the present disclosure. The method illustrated in FIG. 2A to FIG. 6D will be explained with reference to FIG. 1.

(10) Referring to step S10 in FIG. 1 and as illustrated in FIG. 2A, a top wafer 100 and a bottom wafer 200 is provided. In some embodiments, the top wafer 100 includes a substrate 102, an interconnection layer 104, an insulating layer 106 and a dielectric material layer 108. The substrate 102 may be a glass substrate or any other suitable transparent substrate for carrying the components located thereon. The interconnection layer 104 is disposed on the substrate 102 and may include a dielectric layer 104A and a conductive layer 104B. For example, the dielectric layer 104A is disposed on the substrate 102, while the conductive layer 104B is disposed on the dielectric layer 104A. Although only one layer of dielectric layer 104A and one layer of conductive layer 104B are illustrated herein, it should be noted that the number of the dielectric layer 104A and the conductive layer 104B are not limited thereto. In some other embodiments, there are multiple dielectric layers 104A and multiple conductive layers 104B in the interconnection layer 104 for providing electrical connection between components. In some embodiments, the interconnection layer 104 may be electrically connected to various active components (e.g., transistors or the like) or passive components (e.g., resistors, capacitors, inductors or the like) in the top wafer 100 through the conductive layer 104B, or may be used for providing electrical connection to various semiconductor dies or chips (not illustrated).

(11) In some embodiments, the insulating layer 106 is disposed on the interconnection layer 104 and covering the interconnection layer 104. The insulating layer 106 may include insulating materials such as silicon nitride (SiN), or the like. Furthermore, the dielectric material layer 108 is disposed on the insulating layer 106, and may include polymer-based materials such as benzocyclobutene (BCB), or include other dielectric materials, or the like. As illustrated in FIG. 2A, the dielectric material layer 108 includes a top wafer pattern

110. For example, the top wafer pattern **110** includes a plurality of stripe patterns that protrudes into the insulating layer **106**. In other words, the top wafer pattern **110** may be formed by patterning the insulating layer **106** to form a plurality of openings (stripe openings or trenches), and forming the dielectric material layer **108** into the openings to define the top wafer pattern **110**.

(12) As further illustrated in FIG. 2A, in some embodiments, the bottom wafer **200** includes a substrate **202**, a dielectric material layer **208** and a bottom wafer pattern **210**. The substrate **202** may be a glass substrate or any other suitable transparent substrate for carrying the components located thereon. The dielectric material layer **208** is disposed on the substrate **202**, and may include polymer-based materials such as benzocyclobutene (BCB), or include other dielectric materials, or the like. The bottom wafer pattern **210** is disposed on the substrate **202** and covered by the dielectric material layer **208**. In some embodiments, the bottom wafer pattern **210** comprises a bulk pattern, and the bulk pattern is made of metallic material. Similar to the top wafer **100**, the bottom wafer **200** may also include an interconnection layer (not shown) that is electrically connected to various active components (e.g., transistors or the like) or passive components (e.g., resistors, capacitors, inductors or the like) in the bottom wafer **200**, or may be used for providing electrical connection to various semiconductor dies or chips (not illustrated).

(13) Referring to step **S10** in FIG. 1 and as illustrated in FIG. 2B, the top wafer **100** is bonded to the bottom wafer **200**. For example, the dielectric material layer **108** of the top wafer **100** is bonded to the dielectric material layer **208** of the bottom wafer through direct bonding or fusion bonding. In some embodiments, in the bonded wafers, the top wafer pattern **110** of the top wafer **100** may be aligned to the bottom wafer pattern **210** of the bottom wafer **200** to constitute a measurement pattern MP that may be used to evaluate the overlay shift of the bonded wafers. In other words, if there is a shift in the position of the top wafer **100** or bottom wafer **200**, then the measurement pattern MP may be used to evaluate the amount of shift of the bonded wafers.

(14) FIG. 2C is a schematic top view of the measurement pattern MP of the bonded wafers according to one exemplary embodiment of the present disclosure. As illustrated in FIG. 2C, the measurement pattern MP includes the top wafer pattern **110** of the top wafer **100** and the bottom wafer pattern **210** of the bottom wafer **200**. In some embodiments, the top wafer pattern **110** includes a first portion **110-1** and a second portion **110-2**, wherein the first portion **110-1** and the second portion **110-2** constitute an upside-down L-shape pattern. Furthermore, the bottom wafer pattern **210** includes a first part **210-1** and a second part **210-2**, wherein the first part **210-1** and the second part **210-2** constitute an L-shaped pattern. In the exemplary embodiment, the top wafer **100** is bonded to the bottom wafer **200** so that the first portion **110-1** of the top wafer pattern **110** faces the first part **210-1** of the bottom wafer pattern **210**, and that the second portion **110-2** of the top wafer pattern **110** faces the second part **210-2** of the bottom wafer pattern **210**.

(15) In the exemplary embodiment, the top wafer pattern **110** (inclusive of the first portion **110-1** and the second portion **110-2**) includes a plurality of stripe patterns STR, while the bottom wafer pattern **210** (inclusive of the first part **210-1** and the second part **210-2**) includes a bulk pattern BK. However, the disclosure is not limited thereto. In some alternative embodiments, one of the top wafer pattern **110** and the bottom wafer pattern **210** includes the plurality of stripe patterns STR, and another one of the top wafer pattern **110** and the bottom wafer pattern **210** includes the bulk pattern BK. In some other embodiments, both the top wafer pattern **110** and the bottom wafer pattern **210** includes the plurality of stripe patterns STR. In yet another embodiment, both the top wafer pattern **110** and the bottom wafer pattern **210** includes bulk patterns BK.

(16) Based on the different embodiments, it should be noted that the design of the top wafer pattern **110** and the bottom wafer pattern **210** is not particularly limited as long as the patterns may be measured optically using an automatic optical inspection (AOI) device. Furthermore, it should be noted that whether the top wafer pattern **110** and the bottom wafer pattern **210** are stripe patterns STR or bulk patterns BK, this will depend on the material used for forming the patterns. For example, when the top wafer pattern **110** or bottom wafer pattern **210** is a dielectric material pattern (or polymer material pattern), then the top wafer pattern **110**/bottom wafer pattern **210** will include the stripe patterns STR so that the patterns may be optically measured. On the other hand, when the dielectric material pattern (or polymer material pattern) is not made into stripe form, optical measurement of the dielectric material pattern will be difficult. Furthermore, in some embodiments, when the top wafer pattern **110** or bottom wafer pattern **210** is a metallic material pattern, then the top wafer pattern **110**/bottom wafer pattern **210** may include bulk patterns BK that may be directly measured using the automatic optical inspection (AOI) device.

(17) As further illustrated in FIG. 2C, in some embodiments, the first portion **110-1** of the top wafer pattern **110** has a width $Wx1$ measured along a first axis (the X-axis), while the second portion **110-2** of the top wafer pattern **110** has a width $Wy1$ measured along a second axis (the Y-axis). In certain embodiments, the first part **210-1** of the bottom wafer pattern **210** has a width $Wx2$ measured along a first axis (the X-axis), while the second part **210-2** of the bottom wafer pattern **210** has a width $Wy2$ measured along a second axis (the Y-axis). The width $Wx1$ may be larger than the width $Wx2$, while the width $Wy1$ may be larger than the width $Wy2$. In some embodiments, when the top wafer **100** is bonded to the bottom wafer **200** without overlay shift, then the first portion **110-1** of the top wafer pattern **110** and the first part **210-1** of the bottom wafer pattern **210** will be separated by a target distance Dx . Furthermore, the second portion **110-2** of the top wafer pattern **110** and the second part **210-2** of the bottom wafer pattern **210** will be separated by a target distance Dy .

(18) Furthermore, when measuring a shift of the first portion **110-1** of the top wafer **100** relative to the first part **210-1** of the bottom wafer **200** along a first axis (X-axis) by using an optical inspection device, such as an automatic optical inspection device that measures the optical patterns of the top wafer pattern **110** and the bottom wafer pattern **210** automatically, the automatic optical inspection device satisfies the following measurement formulas for measuring overlay shift of the bonded wafers:

(19) $Tx > Dx - Sx$; $Tx < Dx - Sx + Wx2$; $Tx > Sx$; $T < Dx - Sx + Wx1$; wherein, Tx represents a searching distance (searching Torrance setting) for finding an end-point of the first portion **110-1** of the top wafer pattern **110** or an end-point of the first part **210-1** of the bottom wafer pattern **210** using an automatic optical inspection device; and Sx represents an actual shifting amount of the first portion **110-1** of the top wafer pattern **110** along the first axis (X-axis) relative to the target distance Dx .

(20) Similarly, when measuring a shift of the second portion **110-2** of the top wafer **100** relative to the second part **210-2** of the bottom wafer **200** along a second axis (Y-axis) by using the automatic optical inspection device, the automatic optical inspection device satisfies the following measurement formulas for measuring overlay shift of the bonded wafers:

(21) $Ty > Dy - Sy$; $Ty < Dy - Sy + Wy2$; $Ty > Sy$; $Ty < Dy - Sy + Wy1$; wherein, Ty represents a searching distance for finding an end-point of the second portion **110-2** of the top wafer pattern **110** or an end-point of the second part **210-2** of the bottom wafer pattern **210** using an automatic optical inspection device; and Sy represents an actual shifting amount of the second portion **110-2** of the top wafer pattern **110** along the second axis (Y-axis) relative to the target distance Dy .

(22) The detailed method of measuring the overlay shift of the bonded wafers will be described with reference to FIG. 3A to FIG. 6D.

Referring to step S20 in FIG. 1 and as illustrated in FIG. 3A to FIG. 4D, a shift of the first portion **110-1** of the top wafer **100** relative to the first part **210-1** of the bottom wafer **200** along a first axis (X-axis) is measured by performing a first measurement using an automatic optical inspection device.

(23) For example, referring to FIG. 3A, during the first measurement, a target distance D_x is set in an automatic optical inspection device, wherein the target distance D_x is a distance between the first portion **110-1** of the top wafer pattern **110** and the first part **210-1** of the bottom wafer pattern **210** when no shifting of the bonded wafers along the first axis (X-axis) exists. In the exemplary embodiment, the target distance D_x is set by using a standard module having a model first portion **110-M1** and a model first part **210-M1** placed at positions corresponding to the first portion **110-1** and the first part **210-1** where no overlay shift exists.

(24) Referring to FIG. 3B, by using the standard module having the model first portion **110-M1** and the model first part **210-M1** as references, a first target end-point **Ted1** and a second target end-point **Ted2** may be set in the automatic optical inspection device. As shown in FIG. 3B, the first target end-point **Ted1** and the second target end-point **Ted2** corresponds to the relative positions (edges) of the first part **210-1** of the bottom wafer **200** and the first portion **110-1** of the top wafer **100** when no shifting of the bonded wafers exists.

(25) Referring to FIG. 4A, after setting the target distance D_x , the first target end-point **Ted1** and the second target end-point **Ted2** in the automatic optical inspection device, the bonded wafers may be provided to the automatic optical inspection device. Thereafter, the actual shifting amount S_x of the bonded wafers having the measurement pattern **MP** with the first portion **110-1** and the first part **210-1** may be measured. In the exemplary embodiment, in the bonded wafer, the first part **210-1** of the bottom wafer pattern **210** is aligned with the model first part **210-M1** of the standard module so that any shift of the first portion **110-1** of the top wafer pattern **110** relative to the second target end-point **Ted2** may be determined. In other words, the position of the first part **210-1** of the bottom wafer **200** is fixed to the standard module to observe the shift of the top wafer **100**. However, the disclosure is not limited thereto. In another embodiment, the position of the first portion **110-1** of the top wafer **100** is fixed to the standard module to observe the shift of the bottom wafer **200**. That is, the shift of the bonded wafers may be determined by fixing the position of any one of the top wafer pattern **110** or the bottom wafer pattern **210** to the standard module to observe the shift of the other.

(26) Referring to step S21 in FIG. 1 and as illustrated in FIG. 4B, a first search **SR1** is performed based on a searching distance T_x to find a first end-point **Ed1** of the first part **210-1** of the bottom wafer pattern **210** by detecting a dark to light brightness change of the measured pattern. The searching distance T_x may be preliminary set in the automatic optical inspection device. In some embodiments, the first search **SR1** is performed by using the first target end-point **Ted1** as a center point of search and performing a positive value to negative value search with the searching distance T_x . For example, in one embodiment, if the searching distance T_x is set to be $126\ \mu\text{m}$ in the automatic optical inspection device, then $\pm 126\ \mu\text{m}$ search based on the first target end-point **Ted1** as the center point of search will be performed.

(27) Furthermore, in the exemplary embodiment, the first search **SR1** is performed by using the automatic optical inspection device to scan along a first direction **DR1** of the first axis (X-axis) to detect the dark to light brightness change. In the automatic optical inspection device, a light pattern will be observed when the device scans over the top wafer pattern **110** and the bottom wafer pattern **210**, while a dark pattern will be observed when the device scans over areas other than the top wafer pattern **110** and the bottom wafer pattern **210**. Therefore, during the start of the first search **SR1**, a light pattern will be observed due to the scanning over areas of the first portion **110-1**. Thereafter, a dark pattern, a light pattern and another dark pattern will be consecutively observed during the first search **SR1**. In the exemplary embodiment, the first end-point **Ed1** is found when a first “dark to light” brightness change is observed. On the other hand, if a “light to dark” brightness change is first observed, the automatic optical inspection device will determine that this brightness change is not the desired “end-point”, and will continue scanning along the first direction **DR1** to find the first “dark to light” transition.

(28) Referring to step S22 in FIG. 1 and as illustrated in FIG. 4C, after obtaining the first end-point **Ed1**, a second search **SR2** is performed based on the same searching distance T_x to find a second end-point **Ed2** of the first portion **110-1** of the top wafer pattern **110** by detecting a dark to light brightness change of the measured pattern. In some embodiments, the second search **SR2** is performed by using the second target end-point **Ted2** as a center point of search and performing a negative value to positive value search with the searching distance T_x . Furthermore, the second search **SR2** is performed by using the automatic optical inspection device to scan along a second direction **DR2** of the first axis (X-axis) to detect the first dark to light brightness change, wherein the second direction **DR2** is opposite to the first direction **DR1**.

(29) In the exemplary embodiment, during the start of the second search **SR2**, a dark pattern will be observed due to the scanning over areas other than the top wafer pattern **110** and the bottom wafer pattern **210**. Thereafter, a light pattern and a dark pattern will be consecutively observed during the second search **SR2**, and the first “dark to light” brightness change will be determined as the second end-point **Ed2**.

(30) Referring to step S23 in FIG. 1 and as illustrated in FIG. 4D, in a subsequent step, the distance between first end-point **Ed1** and the second end-point **Ed2** is calculated to determine the shift of the first portion **110-1** of the top wafer **100** relative to the first part **210-1** of the bottom wafer **200** along the first axis (X-axis). For example, in some embodiments, the distance between first end-point **Ed1** and the second end-point **Ed2** is calculated to obtain an actual distance D_{ac} between the first portion **110-1** of the top wafer pattern **110** and the first part **210-1** of the bottom wafer pattern **210**. Thereafter, the difference between the actual distance D_{ac} and the target distance D_x is determined to obtain an actual shifting amount S_x of the first portion **110-1** of the top wafer pattern **110** relative to the target distance D_x .

(31) In some embodiments, the automatic optical inspection device calculates the actual distance D_{ac} by counting the number of pixels between the first end-point **Ed1** and the second end-point **Ed2**, and the exact distance may be determined by knowing the pixel size. In certain embodiments, after determining the actual shifting amount S_x , the automatic optical inspection device reports the actual shifting amount S_x (along the X-axis) to the SPC (statistical process control) system for controlling the post wafer-bonding process.

(32) Referring to step S30 in FIG. 1 and as illustrated in FIG. 5A to FIG. 6D, a shift of the second portion **110-2** of the top wafer **100** relative to the second part **210-2** of the bottom wafer **200** along a second axis (Y-axis) is measured by performing a second measurement using the automatic optical inspection device.

(33) For example, referring to FIG. 5A, during the second measurement, a target distance D_y is set in an automatic optical inspection device, wherein the target distance D_y is a distance between the second portion **110-2** of the top wafer pattern **110** and the second part **210-2** of the bottom wafer pattern **210** when no shifting of the bonded wafers along the first axis (X-axis) exists. In the exemplary

embodiment, the target distance D_y is set by using a standard module having a model second portion **110-M2** and a model second part **210-M2** placed at positions corresponding to the second portion **110-2** and the second part **210-2** where no overlay shift exists. The target distance D_y may be the same or different than the target distance D_x , which may be adjusted based on design requirements.

(34) Referring to FIG. 5B, by using the standard module having the model second portion **110-M2** and the model second part **210-M2** as references, a third target end-point **Ted3** and a fourth target end-point **Ted4** may be set in the automatic optical inspection device. As shown in FIG. 5B, the third target end-point **Ted3** and the fourth target end-point **Ted4** corresponds to the relative positions (edges) of the second part **210-2** of the bottom wafer **200** and the second portion **110-2** of the top wafer **100** when no shifting of the bonded wafers exists.

(35) Referring to FIG. 6A, after setting the target distance D_y , the third target end-point **Ted3** and the fourth target end-point **Ted4** in the automatic optical inspection device, the actual shifting amount S_y of the bonded wafers having the measurement pattern **MP** with the second portion **110-2** and the second part **210-2** may be measured. In the exemplary embodiment, in the bonded wafer, the second part **210-2** of the bottom wafer pattern **210** is aligned with the model second part **210-M2** of the standard module so that any shift of the second portion **110-2** of the top wafer pattern **110** relative to the fourth target end-point **Ted4** may be determined. In other words, the position of the second part **210-2** of the bottom wafer **200** is fixed to the standard module to observe the shift of the top wafer **100**. However, the disclosure is not limited thereto, and the shift of the bonded wafers may be determined by fixing the position of any one of the top wafer pattern **110** or the bottom wafer pattern **210** to the standard module to observe the shift of the other.

(36) Referring to FIG. 6B, in a subsequent step, a third search **SR3** is performed based on a searching distance T_y to find a third end-point **Ed3** of the second part **210-2** of the bottom wafer pattern **210** by detecting a dark to light brightness change of the measured pattern. The searching distance T_y may be preliminary set in the automatic optical inspection device, and may be different or same as the searching distance T_x depending on the actual dimensions of the top wafer pattern **110** and the bottom wafer pattern **210**. In some embodiments, the third search **SR3** is performed by using the third target end-point **Ted3** as a center point of search and performing a positive value to negative value search with the searching distance T_y .

(37) Furthermore, in the exemplary embodiment, the third search **SR3** is performed by using the automatic optical inspection device to scan along a third direction **DR3** of the second axis (Y-axis) to detect the dark to light brightness change. For example, during the start of the third search **SR3**, a light pattern will be observed due to the scanning over areas of the second portion **110-2**. Thereafter, a dark pattern, a light pattern and another dark pattern will be consecutively observed during the third search **SR3**, and the first “dark to light” brightness change will be determined as the third end-point **Ed3**.

(38) Referring to FIG. 6C, after obtaining the third end-point **Ed3**, a fourth search **SR4** is performed based on the same searching distance T_y to find a fourth end-point **Ed4** of the second portion **110-2** of the top wafer pattern **110** by detecting a dark to light brightness change of the measured pattern. In some embodiments, the fourth search **SR4** is performed by using the fourth target end-point **Ted4** as a center point of search and performing a positive value to negative value search with the searching distance T_y . Furthermore, the fourth search **SR4** is performed by using the automatic optical inspection device to scan along a fourth direction **DR4** of the second axis (Y-axis) to detect the first dark to light brightness change, wherein the fourth direction **DR4** is opposite to the third direction **DR3**.

(39) In the exemplary embodiment, during the start of the fourth search **SR4**, a dark pattern will be observed due to the scanning over areas other than the top wafer pattern **110** and the bottom wafer pattern **210**. Thereafter, a light pattern and a dark pattern will be consecutively observed during the fourth search **SR4**, and the first “dark to light” brightness change will be determined as the fourth end-point **Ed4**.

(40) Referring to FIG. 6D, in a subsequent step, the distance between third end-point **Ed3** and the fourth end-point **Ed4** is calculated to determine the shift of the second portion **110-2** of the top wafer **100** relative to the second part **210-2** of the bottom wafer **200** along the second axis (Y-axis). For example, in some embodiments, the distance between third end-point **Ed3** and the fourth end-point **Ed4** is calculated to obtain an actual distance D_{ac2} between the second portion **110-2** of the top wafer pattern **110** and the second part **210-2** of the bottom wafer pattern **210**. Thereafter, the difference between the actual distance D_{ac2} and the target distance D_y is determined to obtain an actual shifting amount S_y of the second portion **110-2** of the top wafer pattern **110** relative to the target distance D_y .

(41) In some embodiments, the automatic optical inspection device calculates the actual distance D_{ac2} by counting the number of pixels between the third end-point **Ed3** and the fourth end-point **Ed4**, and the exact distance may be determined by knowing the pixel size. In certain embodiments, after determining the actual shifting amount S_y , the automatic optical inspection device reports the actual shifting amount S_y (along the Y axis) to the SPC (statistical process control) system for controlling the post wafer-bonding process. Up to here, a method for measuring overlay shift of bonded wafers according to some exemplary embodiments of the present disclosure is accomplished.

(42) As described above, the automatic optical inspection device satisfies certain measurement formulas for measuring overlay shift of the bonded wafers, otherwise the measurement will be inaccurate. Examples for deriving the measurement formulas is explained with reference to FIG. 7 and FIG. 8.

(43) FIG. 7 is a schematic top view of one stage in a method for measuring overlay shift of bonded wafers according to some comparative embodiments of the present disclosure. For example, the method is performed according to the steps described in FIG. 4B and FIG. 4C above. The comparative embodiment in FIG. 7 explains why the measurement formulas of $T_x > D_x - S_x$ (searching distance > target distance - actual shifting amount) and $T_x > S_x$ (searching distance > actual shifting amount) should be satisfied.

(44) As illustrated in FIG. 7, in some embodiments, when the searching distance T_x is set to be smaller than a distance difference between the target distance D_x and the actual shifting amount S_x ($D_x - S_x$), and when the searching distance T_x is set to be smaller than the actual shifting amount S_x , then the accurate overlay shifting amount cannot be measured. For example, as shown in FIG. 7, although the first end-point **Ed1** can be accurately found during the first search **SR1**, it can be seen that the second search **SR2** failed to find any end-point. The reason being that the start of the second search **SR2** (with searching distance T_x) is located at a position overlapped with the first portion **110-1** of the top wafer pattern **110**. As such, no “dark to light” brightness change can be observed, and the actual shifting amount S_x cannot be properly determined.

(45) Therefore, taking the first search **SR1** and the second search **SR2** into consideration, the measurement formulas along the first axis (X-axis) should satisfy the following relationship: $T_x > D_x - S_x$ (searching distance > target distance - actual shifting amount) and $T_x > S_x$ (searching distance > actual shifting amount). Similarly, the measurement formulas along the second axis (Y-axis) should satisfy the following relationship: $T_y > D_y - S_y$ (searching distance > target distance - actual shifting amount) and $T_y > S_y$ (searching distance > actual

shifting amount).

(46) FIG. 8 is a schematic top view of one stage in a method for measuring overlay shift of bonded wafers according to some comparative embodiments of the present disclosure. For example, the method is performed according to the steps described in FIG. 4B and FIG. 4C above. The comparative embodiment in FIG. 5 explains why the measurement formulas of $T_x < D_x - S_x + W_{x2}$ (searching distance > target distance - actual shifting amount + width W_{x2} of the first part **210-1**) and $T_x < D_x - S_x + W_{x1}$ (searching distance > target distance - actual shifting amount + width W_{x1} of the first portion **110-1**) should be satisfied.

(47) As illustrated in FIG. 8, in some embodiments, when the searching distance T_x is set to be greater than $D_x - S_x + W_{x2}$ and greater than $D_x - S_x + W_{x1}$, then the accurate overlay shifting amount cannot be measured. For example, as shown in FIG. 8, although the second end-point $Ed1$ can be accurately found during the second search $SR2$, it can be seen that first search $SR1$ failed to correctly determine the first end-point $Ed1$ of the first part **210-1**. The reason being that the searching distance T_x is too large, and the first search $SR1$ would erroneously determine the first “dark to light” brightness change as the first end-point $Ed1$. As such, the actual shifting amount S_x cannot be properly calculated.

(48) Therefore, taking the first search $SR1$ and the second search $SR2$ into consideration, the measurement formulas along the first axis (X-axis) should also satisfy the following relationship: $T_x < D_x - S_x + W_{x2}$ (searching distance > target distance - actual shifting amount + width W_{x2} of the first part **210-1**) and $T_x < D_x - S_x + W_{x1}$ (searching distance > target distance - actual shifting amount + width W_{x1} of the first portion **110-1**). Similarly, the measurement formulas along the second axis (Y-axis) should satisfy the following relationship: $T_y < D_y - S_y + W_{y2}$ (searching distance > target distance - actual shifting amount + width W_{y2} of the second part **210-2**) and $T_y < D_y - S_y + W_{y1}$ (searching distance > target distance - actual shifting amount + width W_{y1} of the second portion **110-2**).

(49) By knowing the following measurement formulas along the first axis (X-axis):

(50) $T_x > D_x - S_x$; $T_x < D_x - S_x + W_{x2}$; $T_x > S_x$; $T_x < D_x - S_x + W_{x1}$; the following relational expression of the measurement formulas can be further derived:

(51) $S_x > D_x - T_x$; $S_x < D_x - T_x + W_{x2}$; $S_x < T_x$; $S_x < D_x - T_x + W_{x1}$.

(52) Similarly, by knowing the following measurement formulas along the second axis (Y-axis):

(53) $T_y > D_y - S_y$; $T_y < D_y - S_y + W_{y2}$; $T_y > S_y$; $T_y < D_y - S_y + W_{y1}$; the following relational expression of the measurement formulas can be further derived:

(54) $S_y > D_y - T_y$; $S_y < D_y - T_y + W_{y2}$; $S_y < T_y$; $S_y < D_y - T_y + W_{y1}$.

(55) FIG. 9 is a schematic top view of a measurement pattern of bonded wafers according to some exemplary embodiments of the present disclosure. In the exemplary embodiment, the target distance D_x between the first portion **110-1** and the first part **210-1** is set as 150 μm , while the width W_{x1} of the first portion **110-1** is set as 100 μm and the width W_{x2} of the first part **210-1** is set as 50 μm .

Under such conditions, and by knowing the measurement formulas beforehand, the relationship between the search distance T_x and the actual shifting amount S_x should be as follows:

(56)

(1) $T_x + S_x < 250 \cdot \text{Math.m}(D_x + W_{x1})$; (2) $T_x < 200 \cdot \text{Math.m}(D_x + W_{x2})$; (3) $T_x > S_x$ (T_x is larger than 125 $\cdot \text{Math.m}$ and S_x is smaller than 125 $\cdot \text{Math.m}$).

(57) Therefore, when the search distance T_x is set to be $\pm 126 \mu\text{m}$, the maximum actual shifting amount S_x measurable is calculated to be $\pm 124 \mu\text{m}$ ($250 \mu\text{m} - 126 \mu\text{m}$). Similarly, the maximum actual shifting amount S_x measurable may be altered depending on the search distance T_x . For example, when the search distance T_x is set to be $\pm 130 \mu\text{m}$, then the maximum actual shifting amount S_x measurable is calculated to be $\pm 120 \mu\text{m}$ ($250 \mu\text{m} - 130 \mu\text{m}$), and when the search distance T_x is set to be $\pm 160 \mu\text{m}$, then the maximum measurable actual shifting amount S_x is calculated to be $\pm 90 \mu\text{m}$ ($250 \mu\text{m} - 160 \mu\text{m}$). Furthermore, by altering the target distance D_x and the widths W_{x1} , W_{x2} , the search distance T_x and actual shifting amount S_x may also be appropriately controlled. The same measurement formulas would also apply when performing measurements along a different axis.

(58) Based on the above, it is noted that the design and dimensions of the top wafer pattern **110** and the bottom wafer pattern **210** may be appropriately adjusted. Furthermore, by adjusting the target distance D_x , the widths (W_{x1} , W_{x2} , W_{y1} and W_{y2}) of the top wafer pattern **110** and the bottom wafer pattern **210** along the first axis and second axis, the search distance T_x and actual shifting amount S_x may be controlled to fulfill different measurement conditions and to meet different product requirements.

(59) In the above-mentioned embodiments, a measurement pattern including a top wafer pattern and a bottom wafer pattern is used for monitoring the overlay shift of bonded wafers. An automatic optical inspection device can be used to monitor the bonded wafers, which will help to automatically report the actual shifting amount of the measurement pattern to the SPC (statistical process control) system. The method has high productivity, and can prevent the manual misjudgment of overlay shift based on visual inspection from the naked eye. Overall, a high throughput measurement method is achieved, which will replace conventional methods based on the visual inspection. The overlay shift of the bonded wafers may also be measured in large quantities, while the quality of the measurement is assured.

(60) In accordance with some embodiments of the present disclosure, a measurement pattern for monitoring overlay shift of bonded wafers includes a top wafer pattern and a bottom wafer pattern. The top wafer pattern includes a first portion with a width W_{x1} measured along a first axis. The bottom wafer pattern includes a first part with a width W_{x2} measured along the first axis, wherein the first portion of the top wafer pattern and the first part of the bottom wafer pattern are separated by a target distance D_x , and wherein the measurement pattern satisfies the following measurement formulas:

(61) $T_x > D_x - S_x$; $T_x < D_x - S_x + W_{x2}$; $T_x > S_x$; $T_x < D_x - S_x + W_{x1}$; wherein, T_x represents a searching distance for finding an end-point of the first portion of the top wafer pattern or an end-point of the first part of the bottom wafer pattern using an automatic optical inspection device; and S_x represents an actual shifting amount of the first portion of the top wafer pattern along the first axis relative to the target distance D_x .

(62) In accordance with some other embodiments of the present disclosure, a method for measuring overlay shift of bonded wafers includes the followings step. A top wafer having a top wafer pattern is provided, the top wafer pattern comprises a first portion and a second portion, wherein the first portion and the second portion constitute an upside-down L-shaped pattern. A bottom wafer having a bottom wafer pattern is provided, the bottom wafer pattern comprises a first part and a second part, wherein the first part and the second part constitute an L-shaped pattern. The top wafer is bonded to the bottom wafer so that the first portion faces the first part, and the second portion faces the second part. A shift of the first portion of the top wafer pattern relative to the first part of the bottom wafer pattern is measured along a first axis by using an automatic optical inspection device, wherein the method includes the following steps: performing a first search based on a searching distance T_x to find a first end-point of the first part of the bottom wafer pattern by

detecting a dark to light brightness change of the measured pattern; performing a second search based on the searching distance Tx to find a second end-point of the first portion of the top wafer pattern by detecting a dark to light brightness change of the measured pattern; and calculating the distance between the first end-point and the second end-point to determine the shift of the first portion of the top wafer relative to the first part of the bottom wafer along the first axis.

(63) In accordance with yet another embodiment of the present disclosure, a method for measuring overlay shift of bonded wafers includes the followings step. A top wafer having a top wafer pattern is bonded onto a bottom wafer having a bottom wafer pattern, wherein the top wafer pattern comprises a first portion with a width Wx1 measured along a first axis, and the bottom wafer pattern comprises a first part with a width Wx2 measured along the first axis. A first measurement is performed by: setting a target distance Dx in an automatic optical inspection device, wherein the target distance Dx is a distance between the first portion of the top wafer pattern and the first part of the bottom wafer pattern when no shifting of the bonded wafers along the first axis exists; setting a searching distance Tx in the automatic optical inspection device; using the automatic optical inspection device to perform a first search based on the searching distance Tx to find a first end-point of the first part of the bottom wafer pattern; using the automatic optical inspection device to perform a second search based on the searching distance Tx to find a second end-point of the first portion of the top wafer pattern; calculating the distance between the first end-point and the second end-point to obtain an actual distance Dac between the first portion of the top wafer pattern and the first part of the bottom wafer pattern; and determining the difference between the actual distance Dac and the target distance Dx to obtain an actual shifting amount Sx of the first portion of the top wafer pattern relative to the target distance Dx.

(64) The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

Claims

1. A method, comprising: bonding a top wafer having a top wafer pattern to a bottom wafer having a bottom wafer pattern; using an optical inspection device for measuring an overlay shift of the top wafer from the bottom wafer along a first axis so that the following measurement conditions are satisfied: $T_x > D_x - S_x$; $T_x < D_x - S_x + W_{x2}$; $T_x > S_x$; $T_x < D_x - S_x + W_{x1}$; wherein, Wx1 is a width of a first portion of the top wafer pattern measured along the first axis; Wx2 is a width of a first part of the bottom wafer pattern measured along the first axis; Dx is a target distance between the first portion and the first part when no shifting of the top wafer and the bottom wafer along the first axis exists; Tx represents a searching distance for finding an end-point of the first portion of the top wafer pattern or an end-point of the first part of the bottom wafer pattern using the optical inspection device; and Sx represents an actual shifting amount of the first portion of the top wafer pattern along the first axis relative to the target distance Dx.
2. The method according to claim 1, wherein using the optical inspection device for measuring the overlay shift of the top wafer from the bottom wafer along the first axis comprises: performing a first search based on the searching distance Tx to find a first end-point of the first part of the bottom wafer pattern by detecting a dark to light brightness change of the measured pattern; performing a second search based on the searching distance Tx to find a second end-point of the first portion of the top wafer pattern by detecting a dark to light brightness change of the measured pattern; and calculating the distance between the first end-point and the second end-point to determine the shift of the first portion of the top wafer relative to the first part of the bottom wafer.
3. The method according to claim 2, further comprising: setting a first target end-point and a second target end-point in the optical inspection device prior to performing the first search and the second search, wherein the first target end-point and the second target end-point corresponds to the relative positions of the first part of the bottom wafer and the first portion of the top wafer when no shifting of the bonded wafers exists, and wherein the first search is performed by using the first target end-point as a center point of search and performing a positive value to negative value search with the searching distance Tx; and the second search is performed by using the second target end-point as a center point of search and performing a negative value to positive value search with the searching distance Tx.
4. The method according to claim 1, further comprising: using the optical inspection device for measuring an overlay shift of the top wafer from the bottom wafer along a second axis that is perpendicular to the first axis so that the following measurement conditions are satisfied: $T_y > D_y - S_y$; $T_y < D_y - S_y + W_{y2}$; $T_y > S_y$; $T_y < D_y - S_y + W_{y1}$; wherein, Wy1 is a width of a second portion of the top wafer pattern measured along the second axis; Wy2 is a width of a second part of the bottom wafer pattern measured along the second axis; Dy is a target distance between the second portion and the second part when no shifting of the top wafer and the bottom wafer along the second axis exists; Ty represents a searching distance for finding an end-point of the second portion of the top wafer pattern or an end-point of the second part of the bottom wafer pattern using the optical inspection device; and Sy represents an actual shifting amount of the second portion of the top wafer pattern along the second axis relative to the target distance Dy.
5. The method according to claim 4, wherein using the optical inspection device for measuring the overlay shift of the top wafer from the bottom wafer along the second axis comprises: performing a third search based on the searching distance Ty to find a third end-point of the second part of the bottom wafer pattern by detecting a dark to light brightness change of the measured pattern; performing a fourth search based on the searching distance Ty to find a fourth end-point of the second portion of the top wafer pattern by detecting a dark to light brightness change of the measured pattern; and calculating the distance between the third end-point and the fourth end-point to determine the shift of the second portion of the top wafer relative to the second part of the bottom wafer.
6. The method according to claim 5, further comprising: setting a third target end-point and a fourth target end-point in the optical inspection device prior to performing the third search and the fourth search, wherein the third target end-point and the fourth target end-point corresponds to the relative positions of the second part of the bottom wafer and the second portion of the top wafer when no shifting of the bonded wafers exists, and wherein the third search is performed by using the third target end-point as a center point of search and performing a positive value to negative value search with the searching distance Ty; and the fourth search is performed by using the fourth target end-point as a center point of search and performing a negative value to positive value search with the searching distance Ty.

7. The method according to claim 1, wherein the top wafer pattern is an upside-down L-shaped pattern including the first portion, and the bottom wafer pattern is a L-shaped pattern including the first part, wherein the first portion is facing the first part after bonding the top wafer to the bottom wafer.

8. A method, comprising: measuring an overlay shift of a first pattern from a second pattern in a bonded wafer using an optical inspection device, comprising: using a first model pattern to simulate a non-shifting position of the first pattern and using a second model pattern to simulate a non-shifting position of the second pattern; setting a first sidewall of the first model pattern as a first target end-point and setting a second sidewall of the second model pattern as a second target end-point, wherein the first sidewall is facing the second sidewall; setting a distance between the first target end-point and the second target end-point as a target distance D_x ; providing the bonded wafer having the first pattern and the second pattern to the optical inspection device, and aligning the first pattern with the first model pattern; and performing a measurement process for determining an actual shifting amount S_x , wherein the actual shifting amount S_x is a distance between an actual sidewall of the second pattern and the second target end-point.

9. The method according to claim 8, wherein performing the measurement process to determine the actual shifting amount S_x comprises: performing a searching process to find a first end-point of the first pattern and a second end-point of the second pattern, and calculating an actual distance D_{ac} between the first end-point and the second end-point; and obtaining the actual shifting amount S_x of the second pattern by determining a difference between the actual distance D_{ac} and the target distance D_x using the optical inspection device.

10. The method according to claim 9, wherein performing the searching process comprises: performing a first search by using the first target end-point as a center point of search and performing a positive value to negative value search to detect a first dark to light brightness change, wherein the first dark to light brightness change in the first search is determined as the first end-point; and performing a second search by using the second target end-point as a center point of search and performing a negative value to positive value search to detect a first dark to light brightness change, wherein the first dark to light brightness change in the second search is determined as the second end-point.

11. The method according to claim 10, wherein the optical inspection device satisfies the following measurement formulas for measuring the shift of the first pattern from the second pattern in a bonded wafer:

$T_x > D_x - S_x$; $T_x < D_x - S_x + W_{x2}$; $T_x > S_x$; $T_x < D_x - S_x + W_{x1}$; wherein, D_x represents the target distance; S_x represents the actual shifting amount; T_x represents a searching distance when performing the positive value to negative value search in the first search, or represents a searching distance when performing the positive value to negative value search in the second search; W_{x1} represents a width of the first pattern measured along a first axis; and W_{x2} represents a width of the second pattern measured along the first axis.

12. The method according to claim 9, wherein the optical inspection device calculates the actual distance D_{ac} by counting the number of pixels between the first end-point and the second end-point.

13. The method according to claim 8, wherein one of the first pattern or the second pattern comprises a plurality of stripe patterns, and another one of the first pattern and the second pattern comprises a bulk pattern.

14. A method, comprising: setting a target distance D_x in an optical inspection device, wherein the target distance D_x is a distance between a first wafer pattern and a second wafer pattern along a first axis when no overlay shift exists; providing a bonded wafer to the optical inspection device, wherein the bonded wafer includes the first wafer pattern and the second wafer pattern arranged along the first axis; measuring a shift of the first wafer pattern and the second wafer pattern in the bonded wafer by: performing a first scan in a first direction along the first axis to find an actual position of the first wafer pattern; performing a second scan in a second direction along the first axis to find an actual position of the second wafer pattern, wherein the second direction is opposite to the first direction; determining an actual distance D_{ac} between the first wafer pattern and the second wafer pattern from the actual position of the first wafer pattern and the actual position of the second wafer pattern; and calculating a difference between the actual distance D_{ac} and the target distance D_x .

15. The method according to claim 14, wherein: finding the actual position of the first wafer pattern comprises finding a position of a first sidewall of the first wafer pattern along the first direction, wherein the position of the first sidewall is determined as a first end-point of the first wafer pattern; and finding the actual position of the second wafer pattern comprises finding a position of a second sidewall of the second wafer pattern along the second direction, wherein the position of the second sidewall is determined as a second end-point of the second wafer pattern, and wherein a distance between the first end-point and the second end-point is determined as the actual distance D_{ac} .

16. The method according to claim 14, wherein finding the actual position of the first wafer pattern comprises finding a first dark to light brightness change in the first scan, and finding the actual position of the second wafer pattern comprises finding a first dark to light brightness change in the second scan.

17. The method according to claim 14, further comprising: setting a first target end-point and a second target end-point in the optical inspection device prior to setting the target distance D_x , wherein the first target end-point and the second target end-point corresponds to the relative positions of the first wafer pattern and the second wafer pattern when no shifting of the bonded wafers exists, and wherein the first scan is performed by using the first target end-point as a center point of search and performing a positive value to negative value search with the searching distance T_x ; and the second scan is performed by using the second target end-point as a center point of search and performing a negative value to positive value search with the searching distance T_x .

18. The method according to claim 14, wherein the first wafer pattern is an upside-down L-shaped pattern of a top wafer, and the second wafer pattern is a L-shaped pattern of a bottom wafer, and the bonded wafer is constituted by bonding the top wafer to the bottom wafer.

19. The method according to claim 14, wherein the optical inspection device satisfies the following measurement formulas for measuring the shift of the first wafer pattern and the second wafer pattern in the bonded wafer:

$T_x > D_x - S_x$; $T_{xx} < D_x - S_x + W_{x2}$; $T_x > S_x$; $T_x < D_x - S_x + W_{x1}$; wherein, D_x represents the target distance; S_x represents an actual shifting amount of the second wafer pattern along the first axis relative to the first wafer pattern; W_{x1} represents a width of the second wafer pattern measured along the first axis; and W_{x2} represents a width of the first wafer pattern measured along the first axis.

20. The method according to claim 14, further comprising: setting a target distance D_y in the optical inspection device, wherein the target distance D_y is a distance between the first wafer pattern and the second wafer pattern along a second axis when no overlay shift exists, and the second axis is perpendicular to the first axis; providing the bonded wafer to the optical inspection device, wherein the bonded wafer includes the first wafer pattern and the second wafer pattern arranged along the first axis and the second axis; measuring

the shift of the first wafer pattern and the second wafer pattern in the bonded wafer by: performing a third scan in a third direction along the second axis to find an actual position of the first wafer pattern; performing a fourth scan in a fourth direction along the second axis to find an actual position of the second wafer pattern, wherein the fourth direction is opposite to the third direction; determining an actual distance D_{ac2} between the first wafer pattern and the second wafer pattern along the second axis from the actual position of the first wafer pattern and the actual position of the second wafer pattern; and calculating a difference between the actual distance D_{ac2} and the target distance D_y .
