

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287800

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

LI; Dachao

DISPLAY SUBSTRATE AND DISPLAY DEVICE

Abstract

A display substrate and a display device are provided. The display substrate includes a sub-pixel and the sub-pixel includes a pixel circuit including a data writing sub-circuit, a storage sub-circuit and a driving sub-circuit. The second capacitor electrode of the storage sub-circuit includes a first protrusion portion and a second protrusion portion which are both protruded along a first direction.

Inventors: LI; Dachao (Beijing, CN)

Applicant: BOE TECHNOLOGY GROUP CO., LTD. (Beijing, CN)

Family ID: 77771498

Appl. No.: 19/216098

Filed: May 22, 2025

Related U.S. Application Data

parent US continuation 18540016 20231214 PENDING child US 19216098

parent US continuation 17430403 20210812 parent-grant-document US 12225785 WO

continuation PCT/CN2020/080240 20200319 child US 18540016

Publication Classification

Int. Cl.: H10K59/131 (20230101); H10K59/121 (20230101)

U.S. Cl.:

CPC H10K59/131 (20230201); G09G2300/0426 (20130101); G09G2300/0833 (20130101); G09G2300/0842 (20130101); G09G2310/08 (20130101); G09G2320/02 (20130101); H10K59/121 (20230201)

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation of U.S. application Ser. No. 18/540,016, filed on Dec. 14, 2023, which is a continuation of U.S. application Ser. No. 17/430,403, filed on Aug. 12, 2021, which is a national stage application of International Application No. PCT/CN2020/080240, filed on Mar. 19, 2020. All the aforementioned patent applications are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

[0002] Embodiments of the present disclosure relate to a display substrate and a display device.

BACKGROUND

[0003] Micro OLED displays involve the combination of organic light-emitting diode (OLED) technology and complementary metal oxide semiconductor (CMOS) technology, and are related to a cross-integration of the optoelectronic industry and the microelectronics industry, micro OLED displays have promoted a development of a new generation of micro display technology, and have also promoted a research and development of organic electronics on silicon, and even a research and development of molecular electronics on silicon.

[0004] Micro OLED displays have excellent display characteristics, such as high resolution, high brightness, rich colors, low drive voltage, fast response speed, and low power consumption, and have broad development prospects.

SUMMARY

[0005] At least an embodiment of the present disclosure provides a display substrate, comprising a base substrate and a first sub-pixel on the base substrate, wherein the first sub-pixel comprises a pixel circuit, and the pixel circuit comprises a data writing sub-circuit, a storage sub-circuit, and a driving sub-circuit, the data writing sub-circuit is electrically connected with a first terminal of the storage sub-circuit, and is configured to transmit a data signal to the first terminal of the storage sub-circuit in response to a control signal, the driving sub-circuit comprises a control electrode, a first electrode and a second electrode, the control electrode of the driving sub-circuit is electrically connected with the first terminal of the storage sub-circuit, the first electrode of the driving sub-circuit is configured to receive a first power supply voltage, and the driving sub-circuit is configured to drive the light-emitting element to emit light in response to a voltage at the first terminal of the storage sub-circuit; the storage sub-circuit comprises a storage capacitor, the storage capacitor comprises a first capacitor electrode and a second capacitor electrode, and the first capacitor electrode and the second capacitor electrode respectively serve as the first terminal and a second terminal of the storage sub-circuit; the second capacitor electrode of the first sub-pixel comprises a first protrusion portion and a second protrusion portion which are both protruded along a first direction.

[0006] In at least one embodiment, the second capacitor electrode comprises a first electrode portion and a second electrode portion which are spaced apart in the first direction; and the first protrusion portion and the second protrusion portion are both a part of the second capacitor electrode.

[0007] In at least one embodiment, the second electrode portion of the second capacitor electrode comprises an electrode protrusion portion, and the electrode protrusion portion is extended along the first direction.

[0008] In at least one embodiment, the display substrate further comprises a second sub-pixel which is adjacent to the first sub-pixel in the first direction, and first electrode portions of second capacitor electrodes of the first sub-pixel and the second sub-pixel are in an integrated structure.

[0009] In at least one embodiment, the pixel circuit further comprises a resistance device, a first terminal of the resistance device is electrically connected with the second electrode of the driving

sub-circuit, and a second terminal of the resistance device is configured to be electrically connected with the light-emitting element; and the resistance device and the control electrode of the driving sub-circuit are in a same layer and insulated from each other, and a resistivity of the resistance device is higher than a resistivity of the control electrode of the driving sub-circuit.

[0010] In at least one embodiment, the resistance device and the control electrode of the driving sub-circuit are both made of a polysilicon material.

[0011] In at least one embodiment, the first sub-pixel further comprises a connection electrode, and the connection electrode electrically connects the first terminal of the resistance device with the second electrode of the driving sub-circuit.

[0012] In at least one embodiment, the connection electrode and the second capacitor electrode are in a same layer and insulated from each other; and the first electrode portion and the second electrode portion of the second capacitor electrode are on opposite sides of the connection electrode.

[0013] In at least one embodiment, the storage capacitor further comprises a third capacitor electrode; and in a direction perpendicular to the base substrate, the third capacitor electrode is on a side of the first capacitor electrode away from the second capacitor electrode, and is configured to be electrically connected with the second capacitor electrode.

[0014] In at least one embodiment, the third capacitor electrode comprises a first electrode protrusion portion protruding along the first direction and a second electrode protrusion protruding along a second direction, and the second direction intersects with the first direction.

[0015] In at least one embodiment, the third capacitor electrode of the storage capacitor is a first region of the base substrate, and the second capacitor electrode is overlapped with the first capacitor electrode in the direction perpendicular to the base substrate.

[0016] In at least one embodiment, the third capacitor electrode comprises an electrode region and a contact region, the electrode region is overlapped with the second capacitor electrode in the direction perpendicular to the base substrate, and the second capacitor electrode is configured to be electrically connected with the electrode region through the contact region; and a doping concentration of the contact region is higher than a doping concentration the electrode region.

[0017] In at least one embodiment, the first capacitor electrode comprises a first protrusion portion and a second protrusion portion which are both protruded in a second direction, and the second direction intersects with the first direction; and the first protrusion portion of the first capacitor electrode serves as the control electrode of the driving sub-circuit.

[0018] In at least one embodiment, the display substrate further comprises a power line extended along the first direction, and the power line is configured to provide the first power supply voltage to the first sub-pixel; and in a direction perpendicular to the base substrate, the power line is overlapped with the second protrusion portion of the second capacitor electrode.

[0019] In at least one embodiment, the display substrate further comprises a power line extended along the first electrode, and the power line is configured to provide a second power supply voltage to the first sub-pixel, and the second power supply voltage is different from the first power supply voltage; and in a direction perpendicular to the base substrate, the power line is overlapped with the first protrusion portion of the second capacitor electrode.

[0020] In at least one embodiment, the data writing sub-circuit comprises a first data writing transistor, the driving sub-circuit comprises a driving transistor, the first data writing transistor is a P-type metal-oxide semiconductor field effect transistor, and the driving transistor is an N-type metal-oxide semiconductor field effect transistor; and in a direction parallel to a plate surface of the base substrate, the first data writing transistor and the driving transistor are on opposite sides of the storage capacitor.

[0021] In at least one embodiment, the first sub-pixel further comprises a connection electrode; the connection electrode and the second capacitor electrode are in a same layer and insulated from each other, and the connection electrode electrically connects the first capacitor electrode with the data

writing sub-circuit.

[0022] In at least one embodiment, the connection electrode comprises a first portion extended along the first direction and a second portion extended along a second direction, the first portion and the second portion are in an integral structure, and the first direction and the second direction are orthogonal to each other; the first portion is electrically connected with the data writing sub-circuit and the second portion is electrically connected with the first capacitor electrode.

[0023] In at least one embodiment, along a second direction, the data writing sub-circuit, the connection electrode and the driving sub-circuit are sequentially arranged, and the first direction and the second direction are orthogonal to each other.

[0024] At least an embodiment of the present disclosure further provides a display device, comprising any one of the above display substrates and the light-emitting element.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0025] In order to clearly illustrate the technical solution of the embodiments of the present disclosure, the drawings of the embodiments will be briefly described. It is apparent that the described drawings are only related to some embodiments of the present disclosure and thus are not limitative of the present disclosure.

[0026] FIG. 1A is a first schematic diagram of a display substrate provided by at least one embodiment of the present disclosure;

[0027] FIG. 1B is a first pixel circuit diagram provided by at least one embodiment of the present disclosure;

[0028] FIG. 1C is a schematic structural diagram of a pixel circuit;

[0029] FIG. 2A is a second pixel circuit diagram provided by at least one embodiment of the present disclosure;

[0030] FIG. 2B is a third pixel circuit diagram provided by at least one embodiment of the present disclosure;

[0031] FIG. 2C is a signal timing diagram of a pixel circuit provided by at least one embodiment of the present disclosure;

[0032] FIG. 3A is a second schematic diagram of a display substrate provided by at least one embodiment of the present disclosure;

[0033] FIG. 3B is a schematic diagram of the display substrate shown in FIG. 3A along a section line I-I';

[0034] FIG. 4A is a third schematic diagram of a display substrate provided by at least one embodiment of the present disclosure;

[0035] FIG. 4B is an enlarged schematic diagram of one sub-pixel of a display substrate provided by at least one embodiment of the present disclosure;

[0036] FIGS. 5A to 5E are diagrams showing the manufacturing steps of the display substrate shown in FIG. 4A;

[0037] FIGS. 6A to 6B are schematic diagrams of a first conductive layer of a display substrate provided by at least one embodiment of the present disclosure;

[0038] FIG. 6C shows a cross-sectional schematic diagram of FIG. 6B along a section line IV-IV';

[0039] FIGS. 7A to 7B are schematic diagrams of a second conductive layer of a display substrate provided by at least one embodiment of the present disclosure;

[0040] FIGS. 8A to 8B are schematic diagrams of a third conductive layer of a display substrate provided by at least one embodiment of the present disclosure;

[0041] FIGS. 9A to 9B are schematic diagrams of a fourth conductive layer of a display substrate provided by at least one embodiment of the present disclosure;

[0042] FIG. 10A is a fourth schematic diagram of a display substrate provided by at least one embodiment of the present disclosure;

[0043] FIG. 10B is an enlarged schematic diagram of a region shown by a dotted line of the display substrate in FIG. 10A;

[0044] FIG. 10C is a cross-sectional schematic diagram of FIG. 10B along a section line V-V';

[0045] FIG. 11A is a fifth schematic diagram of a display substrate provided by at least one embodiment of the present disclosure;

[0046] FIG. 11B is a sixth schematic diagram of a display substrate provided by at least one embodiment of the present disclosure;

[0047] FIG. 11C is a cross-sectional schematic diagram of the display substrate shown in FIG. 11B along a section line II-II';

[0048] FIG. 11D is a cross-sectional schematic diagram of the display substrate shown in FIG. 11B along a section line III-III'; and

[0049] FIG. 12 is a schematic diagram of a display device provided by at least one embodiment of the present disclosure.

DETAILED DESCRIPTION

[0050] In order to make objects, technical details and advantages of embodiments of the present disclosure clear, the technical solutions of the embodiments will be described in a clearly and fully understandable way in connection with the related drawings. It is apparent that the described embodiments are just a part but not all of the embodiments of the present disclosure. Based on the described embodiments herein, those skilled in the art can obtain, without any inventive work, other embodiment(s) which should be within the scope of the present disclosure.

[0051] Unless otherwise defined, all the technical and scientific terms used herein have the same meanings as commonly understood by one of ordinary skill in the art to which the present disclosure belongs. The terms "first," "second," etc., which are used in the description and claims of the present disclosure, are not intended to indicate any sequence, amount or importance, but distinguish various components. The terms "comprises," "comprising," "includes," "including," etc., are intended to specify that the elements or the objects stated before these terms encompass the elements or the objects listed after these terms as well as equivalents thereof, but do not exclude other elements or objects. The phrases "connect", "connected", etc., are not intended to define a physical connection or a mechanical connection, but may comprise an electrical connection which is direct or indirect. The terms "on," "under," "right," "left" and the like are only used to indicate relative position relationship, and in a case that the position of an object is described as being changed, the relative position relationship may be changed accordingly.

[0052] In the field of OLED (Organic Light-Emitting Diode) display, with the rapid development of high-resolution products, higher requirements are put forward for a structural design of a display substrate, such as an arrangement of pixels and signal lines. For example, compared to an OLED display device with a resolution of 4K, the number of sub-pixel units that need to be arranged in a large-size 8K resolution OLED display device is doubled, and a pixel density is doubled accordingly; on one hand, a line width of the signal line is correspondingly smaller, which leads to an increase of a self-resistance of the signal line; on the other hand, more overlapping regions exist between signal lines, which leads to an increase of parasitic capacitance of the signal lines, thus leading to an increase of resistance capacitance load of the signal lines. Correspondingly, signal delay (RC delay), voltage drop (IR drop), voltage rise (IR rise) and other phenomena caused by the resistance capacitance load of the signal lines also become serious. These phenomena seriously affect a display quality of a display product.

[0053] A micro OLED display usually has a size of less than 100 microns, such as a size less than 50 microns, and involves a combination of organic light-emitting diode (OLED) technology and CMOS technology, which manufactures an OLED array on a silicon-based substrate including CMOS circuits.

[0054] Micro OLEDs are widely used in fields of AR and VR. With the continuous development of technology, higher resolutions are required for the Micro OLEDs. Therefore, higher requirements are put forward for the structural design of the display substrate, such as the arrangement of the pixels and the signal lines.

[0055] A display substrate provided by at least one embodiment of the present disclosure can achieve a sub-pixel area of $5.45\text{ }\mu\text{m}\times 13.6\text{ }\mu\text{m}$ by an optimized layout and wiring design processing in the design, which realizes a pixel circuit array with a high resolution (PPI) and an optimized arrangement, and achieves a better display effect.

[0056] FIG. 1A is a block diagram of a display substrate provided by at least one embodiment of the present disclosure. As shown in FIG. 1A, the display substrate **10** includes a plurality of sub-pixels **100** arranged in an array, a plurality of scan lines **11**, and a plurality of data lines **12**. Each of the plurality of sub-pixels **100** includes a light-emitting element and a pixel circuit that drives the light-emitting element. The plurality of scan lines **11** and the plurality of data lines **12** cross each other to define a plurality of pixel regions distributed in an array in a display region, and a pixel circuit of a sub-pixel **100** is provided in each of the plurality of pixel regions. The pixel circuit is, for example, a conventional pixel circuit, such as a 2T1C (that is, two transistors and a capacitor) pixel circuit, a 4T2C pixel circuit, a 5T1C pixel circuit, a 7T1C pixel circuit and other nTmC (n, m are positive integers) pixel circuits, and in different embodiments, the pixel circuit may further include a compensation sub-circuit, the compensation sub-circuit includes an internal compensation sub-circuit or an external compensation sub-circuit, and the compensation sub-circuit may include a transistor and a capacitor and so on. For example, according to needs, the pixel circuit may further include a reset circuit, a light-emitting control sub-circuit, and a detection circuit. For example, the display substrate may further include a gate driving sub-circuit **13** and a data driving sub-circuit **14** located in a non-display region. The gate driving sub-circuit **13** is connected with the pixel circuit through the scan lines **11** to provide various scanning signals, and the data driving sub-circuit **14** is connected with the pixel circuit through the data lines **12** to provide data signals. Positional relationships between the gate driving sub-circuit **13** and the data driving sub-circuit **14**, and between the scan lines **11** and the data lines **12** shown in FIG. 1A are only exemplary, and actual arrangement and positions can be designed as required.

[0057] For example, the display substrate **10** may further include a control circuit (not shown). For example, the control circuit is configured to control the data driving sub-circuit **14** to apply the data signals and to control the gate driving sub-circuit to apply the scanning signals. An example of the control circuit is a timing control circuit (T-con). The control circuit can be in various forms, for example, including a processor and a memory, the memory includes an executable code, and the processor runs the executable code to execute the above detection method.

[0058] For example, the processor may be a central processing unit (CPU) or other form of processing device with data processing capability and/or instruction execution capability, for example, may include a microprocessor, a programmable logic controller (PLC), and so on.

[0059] For example, the storage device may include one or more computer program products, the computer program products may include various forms of computer-readable storage media, such as a volatile memory and/or a non-volatile memory. The volatile memory may include, for example, a random access memory (RAM) and/or a cache memory. The non-volatile memory may include, for example, a read-only memory (ROM), a hard disk, a flash memory, and so on. One or more computer program instructions can be stored on a computer-readable storage medium, and the processor can execute functions expected by the program instructions. Various application programs and various data can also be stored in the computer-readable storage medium.

[0060] The pixel circuit may include a driving sub-circuit, a data writing sub-circuit, a compensation sub-circuit and a storage sub-circuit as required, and may further include a light-emitting control sub-circuit, and a reset circuit as required.

[0061] FIG. 1B shows a schematic diagram of a pixel circuit. As shown in FIG. 1B, the pixel

circuit includes a data writing sub-circuit **111**, a driving sub-circuit **112**, and a storage sub-circuit **113**.

[0062] The data writing sub-circuit **111** is electrically connected with a first terminal of the storage sub-circuit **113**, and is configured to transmit a data signal V_d to the first terminal of the storage sub-circuit **113** in response to a control signal (a first control signal SEL). A second terminal of the storage sub-circuit **113** is, for example, configured to receive a second power voltage VSS.

[0063] The driving sub-circuit **112** includes a control electrode **150**, a first electrode **151** and a second electrode **152**. The control electrode (control terminal) **150** of the driving sub-circuit is electrically connected with the first terminal of the storage sub-circuit, the first electrode (first terminal) **151** of the driving sub-circuit **112** is configured to receive a first power voltage VDD, the second electrode (second terminal) **152** of the driving sub-circuit **112** is electrically connected with a first node S, and is connected with a first electrode **121** of a light-emitting element **120**. The driving sub-circuit **112** is configured to drive the light-emitting element **120** to emit light in response to a voltage at the first terminal of the storage sub-circuit. A second electrode **122** of the light-emitting element **120** is, for example, configured to receive a first common voltage V_{com1} .

[0064] In at least some embodiments of the present disclosure, as shown in FIG. **1B**, the pixel circuit further includes a bias sub-circuit **114**. The bias sub-circuit **114** includes a control terminal, a first terminal and a second terminal, the control terminal of the bias sub-circuit **114** is configured to receive a bias signal; the first terminal of the bias sub-circuit **114** is configured to, for example, receive the second power voltage VSS, the second terminal of the bias sub-circuit **114** is electrically connected with the first node S. For example, the bias signal is a second common voltage V_{com2} . For example, the bias signal V_{com2} is a constant voltage signal, for example, ranging from 0.8V to 1V; the bias sub-circuit **114** is normally open under the action of the bias signal, and is configured to provide a constant current, so that the voltage applied to the light-emitting element **120** has a linear relationship with the data signal, which helps to achieve a fine control of a gray scale, thereby improving a display effect. This will be further explained in the following text in conjunction with specific circuits.

[0065] For example, in the case that the data signal (voltage) V_d changes from high to low, a gray-scale voltage written in the first electrode **121** of the light-emitting element **120** needs to change rapidly, and the bias sub-circuit **114** can also allow the first electrode **121** of the light-emitting element **120** to release charges quickly, thereby achieving better dynamic contrast.

[0066] The transistors used in the embodiments of the present disclosure may all be thin film transistors or field effect transistors or other switching devices with the same characteristics, in the embodiments of the present disclosure, metal-oxide semiconductor field effect transistors are taken as examples for description. A source electrode and a drain electrode of a transistor used herein can be symmetrical in structure, so that there is no difference between the source electrode and the drain electrode of the transistor in structure. In the embodiments of the present disclosure, in order to distinguish the two electrodes of the transistor other than a gate electrode, one electrode is directly described as a first electrode, and the other electrode is a second electrode. In addition, transistors can be divided into an N-type transistor and a P-type transistor according to their characteristics. In a case that the transistor is the P-type transistor, a turn-on voltage is a low-level voltage (for example, 0V, -5V, -10V or other suitable voltages), and an off voltage is a high-level voltage (for example, 5V, 10V or other suitable voltage); in a case that the transistor is the N-type transistor, the turn-on voltage is a high-level voltage (for example, 5V, 10V or other suitable voltage), and the off voltage is a low-level voltage (for example, 0V, -5V, -10V or other suitable voltages).

[0067] The display substrate provided by the embodiments of the present disclosure may adopt a rigid substrate, such as a glass substrate, a silicon substrate, etc., and can also be formed of flexible materials with excellent heat resistance and durability, such as polyimide (PI), polycarbonate (PC), polyethylene terephthalate (PET), polyethylene, polyacrylate, polyaryl compounds, polyetherimide,

polyethersulfone, polyethylene glycol terephthalate (PET), polyethylene (PE), polypropylene (PP), polysulfone (PSF), polymethyl methacrylate (PMMA), triacetyl cellulose (TAC), cyclic olefin polymer (COP) and cyclic olefin copolymer (COC), etc. The embodiments of the present disclosure are described by taking a silicon substrate as an example, that is, the pixel structure is manufactured on the silicon substrate, however, the embodiment of the present disclosure are not limited thereto.

[0068] For example, the pixel circuit includes a complementary metal oxide semiconductor circuit (CMOS circuit), that is, the pixel circuit is manufactured on a monocrystal silicon substrate. Relying on mature CMOS integrated circuit technology, silicon-based technology can achieve higher accuracy (for example, the PPI can reach 6,500 or even more than 10,000).

[0069] For example, in the case that a short circuit occurs between the first electrode **121** and the second electrode **122** of the light-emitting element **120** in the sub-pixel due to process fluctuations of the display substrate, the voltage of the first electrode **121** of the light-emitting element **120** is too high (for example, the first common voltage Vcom1 is at a high potential) or too low (for example, the first common voltage Vcom1 is at a low potential), causing a PN junction between the second electrode of the driving circuit and the base substrate to turn on, and causing failure of the CMOS circuit, and resulting in defects such as dark lines in the display substrate.

[0070] In some examples, for example, the data writing sub-circuit includes a first data writing transistor **P1**, and the driving sub-circuit includes a driving transistor **N2**; for example, the first data writing transistor is a P-type metal-oxide semiconductor field effect transistor (PMOS), the driving transistor **N2** is an N-type metal-oxide semiconductor field effect transistor (NMOS), a gate electrode, a first electrode, and a second electrode of the driving transistor **N2** serve as the control electrode **150**, the first electrode **151** and the second electrode **152** of the driving sub-circuit **112**, respectively. In this case, for example, in a case that the first common voltage Vcom1 supplied to the second electrode **122** of the light-emitting element **120** is at a low potential, and the first electrode **121** and the second electrode **122** of the light-emitting element **120** are short circuited, the potential of the second electrode of the driving transistor directly connected with the first electrode **121** is caused to be too low.

[0071] FIG. 1C shows a schematic diagram of the failure of the transistors in the pixel circuit. An N-type active region (such as the second electrode) of the driving transistor **N2**, a P-type silicon-based substrate, an N-type well region where the first data writing transistor **P1** is located, and a P-type active region (such as the first electrode) of the first data writing transistor **P1** form two parasitic transistors **Q1** and **Q2** that are connected with each other, which forms an N-P-N-P structure. In the case that the potential of the second electrode (that is, the first node S) of the driving transistor **N2** is too low, causing a PN junction (a transmitting junction) between the second electrode (a heavily-doped N-type region) of the driving transistor **N2** and the P-type substrate to be positively biased and **Q1** to be turned on, which provides a current large enough to turn on the parasitic transistor **Q2**; in turn, the parasitic transistor **Q2** feeds back a current to the parasitic transistor **Q1**, to form a vicious circle, finally most of the current flows directly from VDD to VSS through the parasitic transistors without being controlled by the gate voltage of the transistor, which causes the CMOS pixel circuit to fail; in addition, the failure of the circuit will cause the parasitic transistor **Q2** to continuously draw a current from a emitter, i.e., the data line, thereby causing a column of sub-pixels connected with the data line to fail, and causing defects such as a dark line on the display substrate, which greatly affects the display effect.

[0072] In at least some embodiments of the present disclosure, at least one sub-pixel further includes a resistance device, the resistance device is connected between the second electrode **152** of the driving sub-circuit **112** and the first electrode **121** of the light-emitting element **120**, and the resistance device can increase or decrease the potential of the first node S, so that the latch-up effect can be relieved or avoided, the reliability of the circuit can be improved, and the display effect can be improved.

[0073] FIG. 2A is a schematic diagram of a pixel circuit provided by at least one embodiment of the present disclosure. As shown in FIG. 2A, the pixel circuit further includes the resistance device **130**, the first terminal **131** of the resistance device **130** is electrically connected with the second electrode **152** of the driving sub-circuit **112**, and the second terminal **132** is electrically connected with the first electrode **121** of the light-emitting element **120**, that is, the second electrode **152** of the driving sub-circuit **112** is electrically connected with the first electrode **121** of the light-emitting element **120** through the resistance device **130**.

[0074] For example, the resistance device **130** is a constant resistor or a variable resistor, and may also be an equivalent resistor formed by other devices (such as a transistor).

[0075] For example, the resistance device **130** and the control electrode **150** of the driving sub-circuit **112** are arranged in a same layer and insulated from each other, and a resistivity of the resistance device is higher than a resistivity of the control electrode of the driving sub-circuit; that is, a conductivity of the control electrode of the driving sub-circuit is higher than a conductivity of the resistance device. For example, the resistivity of the resistance device is more than ten times of the resistivity of the control electrode.

[0076] It should be noted that the “in a same layer” mentioned in the present disclosure refers to forming two (or more than two) structures through a same deposition process and patterning them through a same patterning process, and the materials of the structures can be the same or different. For example, the materials for forming precursors of the structures arranged in the same layer are the same, and the finally formed materials may be the same or different. The “an integrated structure” in the present disclosure refers to an interconnected structure formed by forming two (or more than two) structures through a same deposition process and patterning them through a same patterning process, and the materials of the structures can be the same or different.

[0077] Through this arrangement, the control electrode of the driving sub-circuit and the resistance device can be formed in the same patterning process, thereby saving process.

[0078] For example, both a material of the resistance device and a material of the control electrode of the driving sub-circuit are polysilicon materials, and a doping concentration of the resistance device is lower than a doping concentration of the control electrode, thus the resistance device has a higher resistivity than the control electrode. For example, the resistance device may be intrinsic polysilicon or lightly doped polysilicon, and the control electrode may be heavily doped polysilicon.

[0079] In other examples, the material of the control electrode is different from the material of the resistance device. For example, the material of the control electrode may include a metal and the material of the resistance device may comprise a metal oxide corresponding to the metal. For example, the metal may include gold (Au), silver (Ag), copper (Cu), aluminum (Al), molybdenum (Mo), magnesium (Mg), tungsten (W), and alloy materials composed of the above metals.

[0080] In at least one embodiment of the present disclosure, the data writing sub-circuit **111** may include a transmission gate circuit composed of two complementary transistors in parallel connection with each other; the control signal includes two inverted control signals. The data writing sub-circuit **111** adopts a circuit in a transmission gate structure, which can help to transmit the data signal to the first terminal of the storage sub-circuit **113** with no loss.

[0081] For example, the data writing sub-circuit includes a first control electrode, a second control electrode, a first terminal and a second terminal, the first control electrode and the second control electrode of the data writing sub-circuit are respectively configured to receive a first control signal and a second control signal, the first terminal of the data writing sub-circuit is configured to receive a data signal, and the second terminal of the data writing sub-circuit is electrically connected to the first terminal of the storage sub-circuit, and is configured to transmit the data signal to the first terminal of the storage sub-circuit in response to the first control signal and the second control signal.

[0082] It should be noted that in the description of the embodiments of the present disclosure, the

first node S does not necessarily represent an actual component, but represents a junction for connecting related circuits in a circuit diagram.

[0083] It should be noted that in the description of the embodiments of the present disclosure, the symbol Vd can represent both the data signal terminal and a level of the data signal, similarly, the symbol SEL can represent both a control signal and a control signal terminal, the symbols Vcom1 and Vcom2 can represent a first common voltage and a second common voltage, and can also represent a first common voltage terminal and a second common voltage terminal; the symbol VDD can represent both a first voltage terminal and a first power voltage, and the symbol VSS can represent both a second voltage terminal and a second power voltage. The case is the same in the following embodiments and is not repeated.

[0084] FIG. 2B shows a circuit diagram of a specific implementation example of the pixel circuit shown in FIG. 2A. As shown in FIG. 2B, the data writing sub-circuit **111** includes a first data writing transistor P1 and a second data writing transistor N1 that are connected in parallel with each other. The first data writing transistor P1 and the second data writing transistor N1 are a P-type metal-oxide semiconductor field effect transistor (PMOS) and an N-type metal-oxide semiconductor field effect transistor (NMOS), respectively. The control signal includes a first control signal SEL and a second control signal SEL_B that are inverted to each other, a gate electrode of the first data writing transistor P1 serves as the first control electrode of the data writing sub-circuit, and is configured to receive the first control signal SEL, a gate electrode of the second data writing transistor N1 serves as the second control electrode of the data writing sub-circuit, and is configured to receive the second control signal SEL_B. The first electrode of the second data writing transistor N1 and the first electrode of the first data writing transistor P1 are electrically connected and serve as the first terminal of the data writing sub-circuit, and are configured to receive a data signal Vd; the second electrode of the second data writing transistor N1 and the second electrode of the first data writing transistor P1 are electrically connected and serve as the second terminal of the data writing sub-circuit, and is electrically connected with the control electrode **150** of the driving sub-circuit **112**.

[0085] For example, the first data writing transistor P1 and the second data writing transistor N1 have a same size and a same channel width to length ratio.

[0086] The data writing sub-circuit **111** take advantages of the complementary electrical characteristics of the transistors and has a low on-state resistance regardless of whether transmitting a high level or a low level, so that the data writing sub-circuit **111** has an advantage of electrical signal integrity in the transmission, and can transmit the data signal Vd to the first terminal of the storage sub-circuit **113** without loss.

[0087] For example, as shown in FIG. 2B, the driving sub-circuit **112** includes a driving transistor N2, for example, the driving transistor N2 is NMOS. The gate electrode, the first electrode and the second electrode of the driving transistor N2 serve as the control electrode, the first electrode and the second electrode of the driving sub-circuit **112**, respectively.

[0088] For example, the storage sub-circuit **113** includes a storage capacitor Cst, the storage capacitor Cst includes a first capacitor electrode **141** and a second capacitor electrode **142**, and the first capacitor electrode **141** and the second capacitor electrode **142** serve as the first terminal and the second terminal of the storage sub-circuit **113**, respectively.

[0089] For example, the resistance device **130** includes a resistor R. For example, a PN junction is formed between the second electrode **152** of the driving sub-circuit **112** and the base substrate, a resistance value of the resistance device **130** is configured that in a case that the driving transistor N2 is operating in a saturation region, that is, in a case that the pixel circuit operates to drive the light-emitting element **120** to emit light, the PN junction is turned off. In this situation, even if a short circuit occurs between the two electrodes of the light-emitting element **120**, because a voltage drop is occurred on the resistance device **130**, the potential of the second electrode **152** can be protected, so that the occurrence of the failure of the circuit is avoided.

[0090] For example, the resistance value R of the resistance device **130** meets:

$R > |V_s - V_{on} - V_{com1}| / I_s$, where V_s is a bias voltage of the base substrate, V_{com1} is the first common voltage provided for the second electrode of the light-emitting element, V_{on} is the turn-on voltage of the PN junction, and I_s is a saturation current of the driving transistor **N2** working in the saturation region, that is $\frac{1}{2} \mu_{sub.n} C_{sub.ox} W/L (V_{gs} - V_{th})^2$, where $\mu_{sub.n}$ is a carrier mobility of the driving transistor, $C_{sub.ox}$ is a capacitance per unit area of the gate insulating layer, W/L is a width to length ratio of the channel region, V_{gs} is a voltage difference between the gate electrode and the source electrode of the driving transistor, and V_{th} is a threshold voltage of the driving transistor. For example, the turn-on voltage V_{on} ranges from 0.6 V to 0.7V. Through the above arrangement, it can be ensured that the PN junction formed between the second electrode **152** of the driving sub-circuit **112** and the base substrate is turned off in a case that the driving transistor **N2** is working in the saturation region.

[0091] For example, the light-emitting element **120** is specifically implemented as an organic light-emitting diode (OLED). For example, the light-emitting element **120** may be an OLED with a top emitting structure, which may emit red light, green light, blue light, or white light. For example, the light-emitting element **120** is a micro OLED. The embodiments of the present disclosure do not limit the specific structure of the light-emitting element. For example, the first electrode **121** of the light-emitting element **120** is an anode of the OLED, the second electrode **122** is a cathode of the OLED, that is, the pixel circuit has a common cathode structure. However, the embodiments of the present disclosure are not limited thereto; the pixel circuit may also be in a common anode structure according to the change of the circuit structure.

[0092] For example, the bias sub-circuit **114** includes a bias transistor **N3**, and the gate electrode, the first electrode and the second electrode of the bias transistor **N3** serve as the control terminal, the first terminal and the second terminal of the bias sub-circuit **114**, respectively.

[0093] FIG. 2C shows a signal timing diagram of the pixel circuit shown in FIG. 2B, the working principle of the pixel circuit shown in FIG. 2C is described below in conjunction with the signal timing diagram shown in FIG. 2B. For example, the second data writing transistor, the driving transistor, and the bias transistor are all N-type transistors, and the first data writing transistor is a P-type transistor, however, the embodiments of the present disclosure are not limited thereto.

[0094] FIG. 2C shows waveform diagrams of each signal in two consecutive display periods **T1** and **T2**, for example, the data signal V_d is a high gray-scale voltage during the display period **T1**, and the data signal V_d is a low gray-scale voltage during the display period **T2**.

[0095] For example, as shown in FIG. 2C, a display process of each frame of image includes a data writing stage **1** and a light-emitting stage **2**. A working process of the pixel circuit includes: in the data writing stage **1**, both the first control signal SEL and the second control signal SEL_B are turn-on signals, the first data writing transistor **P1** and the second data writing transistor **N1** are turned on, the data signal V_d is transmitted to the gate electrode of the driving transistor **N2** through the first data writing transistor **P1** and the second data writing transistor **N1**; in the light-emitting stage **2**, both the first control signal SEL and the second control signal SEL_B are off signals, due to a bootstrap effect of the storage capacitor C_{st} , the voltage across the storage capacitor C_{st} remains unchanged, the driving transistor **N2** works in a saturated state and has an unchanged current, and drives the light-emitting element **120** to emit light. In a case that the pixel circuit enters the display period **T2** from the display period **T1**, the data signal V_d changes from a high gray-scale voltage to a low gray-scale voltage, the bias transistor **N3** under the control of the second common voltage V_{com2} generates a stable drain current which can quickly discharge the charge stored in the anode of the OLED in a case that the display gray scale of the OLED needs to change rapidly. For example, the discharge process occurs during data writing stage **1** in the display period **T2**, and thus in the light-emitting stage **2** of the display period **T2**, the voltage of the anode of the OLED can be rapidly reduced, so that a better dynamic contrast is achieved, and the display effect is improved.

[0096] Referring to FIG. 2B, for example, in the light-emitting stage, a light-emitting current of the light-emitting element OLED is on the order of nanoamperes (for example, a few nanoamperes) in a case that the light-emitting element OLED is written in a gray-scale data, while the bias transistor N3 generates a current generated on the order of microamperes (for example, 1 microampere) while working in the saturation region under the control of the bias signal, i.e. the second common voltage Vcom2, and thus almost all the current flowing through the driving transistor N2 flows into the bias transistor N3, the current of the driving transistor N2 and the current of the bias transistor N3 can be regarded as the same, that is

$$[00001] \frac{1}{2} \mu_n C_{ox} W / L (V_{gs1} - V_{th1})^2 = \frac{1}{2} \mu_n C_{ox} W / L (V_{gs2} - V_{th2})^2,$$

here it is assumed that the driving transistor N2 and the bias transistor N3 have a same transistor conductivity $\mu_{n,sub} C_{ox} W / L$, then it is obtained that $V_{gs1} - V_{th1} = V_{gs2} - V_{th2}$, in which V_{gs1} and V_{th1} are the voltage difference V_{gs1} between the gate electrode and the source electrode of the driving transistor N2 and the threshold voltage of the driving transistor N2, respectively; V_{gs2} and V_{th2} are the voltage difference between the gate electrode and the source electrode of the bias transistor N3 and the threshold voltage of the bias transistor N3, respectively; and because $V_{gs2} - V_{th2} = V_{com2} - V_{SS} - V_{th2}$, which is a fixed value, denoted as $K0$, that is, $V_{gs1} - V_{th1} = K0$, that is, $V_d - V_0 - V_{th1} = K0$, in which V_d is the data signal held at the gate electrode of the driving transistor N2 during the light-emitting stage, V_0 is the voltage at the first node S. In this way, it can be concluded that the voltage V_0 at the first node S has a linear relationship with the data signal (data voltage) V_d .

[0097] For example, the bias transistor N3 works in a saturation region under the control of the bias signal Vcom2, and a difference between a voltage of the gate electrode and a voltage of the source electrode of the bias transistor is $V_{com2} - V_{SS}$ and is a fixed value; according to the above formula of a current of the transistor in a saturation region, the current flowing through the bias transistor N3 in this situation is a constant current, so the bias transistor N3 can be regarded as a current source.

[0098] For example, in the case that the first node S is directly electrically connected with the light-emitting element 120, the voltage V_0 is directly applied to the first electrode 121 of the light-emitting element 120, and is an anode voltage of the OLED for example; in a case that the first node S is electrically connected with the light-emitting element 120 through the resistance device 130, because the current flowing through the light-emitting element 120 is extremely small, a voltage of the first node S can be approximately equal to a voltage of the first electrode 121 of the light-emitting element 120; that is, the voltage of the first electrode 121 of the light-emitting element 120 is in a linear relationship with the data signal (data voltage) V_d , so that a fine control of the gray scale can be realized, and the display effect can be improved.

[0099] For example, the first control signal SEL and the second control signal SEL_B are differential complementary signals with a same amplitude but opposite phases, which helps to improve an anti-interference performance of the circuit. For example, the first control signal SEL and the second control signal SEL_B can be output by a same gate driving circuit unit (such as a GOA unit), thereby simplifying the circuit.

[0100] For example, as shown in FIG. 1A, the display substrate 10 may further include a data driving circuit 13 and a scan driving circuit 14. The data driving circuit 13 is configured to send out a data signal, such as the above-mentioned data signal V_d , as required (for example, inputting an image signal to the display device). The scan driving circuit 14 is configured to output various scanning signals, for example, including the above-mentioned first control signal SEL and second control signal SEL_B, for example, the scan driving circuit 14 is an integrated circuit chip (IC) or a gate driving circuit (GOA) directly manufactured on the display substrate.

[0101] For example, the display substrate uses a silicon substrate as the base substrate 101, the pixel circuit, the data driving circuit 13 and the scan driving circuit 14 can all be integrated on the silicon substrate. In this case, since the silicon-based circuit can achieve a higher accuracy, the data

driving circuit **13** and the scan driving circuit **14** may also be formed, for example, in a region corresponding to the display region of the display substrate, and are not necessarily located in the non-display region.

[0102] For example, the display substrate **10** further includes a control circuit (not shown). For example, the control circuit is configured to control the data driving circuit **13** to apply the data signal V_d , and to control the gate driving circuit **13** to apply various scanning signals. An example of the control circuit is a timing control circuit (T-con). The control circuit can be in various forms, for example, including a processor and a memory, the memory includes executable code, and the processor runs the executable code to execute the above detection method.

[0103] For example, the processor may be a central processing unit (CPU) or another form of processing device with data processing capability and/or instruction execution capability, for example, may include a microprocessor, a programmable logic controller (PLC), and so on.

[0104] For example, the storage device may include one or more computer program products, the computer program product may include various forms of computer-readable storage media, such as a volatile memory and/or a non-volatile memory. The volatile memory may include, for example, a random access memory (RAM) and/or a cache memory. The non-volatile memory may include, for example, a read-only memory (ROM), a hard disk, a flash memory, and so on. One or more computer program instructions can be stored on a computer-readable storage medium, and the processor **121** can execute functions expected by the program instructions. Various application programs and various data can also be stored in the computer-readable storage medium, for example, the electrical characteristic parameters obtained in the above detection method.

[0105] The following uses the pixel circuit shown in FIG. **2B** as an example to illustrate the display substrate provided by at least one embodiment of the present disclosure, but the embodiments of the present disclosure are not limited thereto.

[0106] FIG. **3A** is a schematic diagram of a display substrate **10** provided by at least one embodiment of the present disclosure. For example, as shown in FIG. **3A**, the display substrate **10** includes a base substrate **101**, and a plurality of sub-pixels **100** are located on the base substrate **101**. The plurality of sub-pixels **100** are arranged as a sub-pixel array, a row direction of the sub-pixel array is a first direction **D1**, a column direction of the sub-pixel array is a second direction **D2**, and the first direction **D1** intersects the second direction **D2**, for example, the first direction **D1** is orthogonal to the second direction **D2**. FIG. **3A** exemplarily shows two rows and six columns of sub-pixels, that is, two pixel rows **20** and six pixel columns **30**, and uses dashed-line frames to respectively show the regions of three pixel columns spaced apart from each other.

[0107] For example, the base substrate **101** may be a rigid substrate, such as a glass substrate, a silicon substrate, etc., and can also be formed of flexible materials with excellent heat resistance and durability, such as polyimide (PI), polycarbonate (PC), polyethylene terephthalate (PET), polyethylene, polyacrylate, polyaryl compounds, polyetherimide, polyether Sulfone, polyethylene glycol terephthalate (PET), polyethylene (PE), polypropylene (PP), polysulfone (PSF), polymethyl methacrylate (PMMA), triacetyl cellulose (TAC), cyclic olefin polymer (COP) and cyclic olefin copolymer (COC), etc. The embodiments of the present disclosure are described by always taking the base substrate **101** as a silicon substrate as an example, however, the embodiment of the present disclosure does not limit to this.

[0108] For example, the base substrate **101** includes monocrystal silicon or high-purity silicon. The pixel circuit is formed on the base substrate **10** through a CMOS semiconductor process, for example, an active region of the transistor (including the channel region, the first electrode and the second electrode of the transistor) is formed in the base substrate **101** through a doping process, each insulating layer is formed by a silicon oxidation process or a chemical vapor deposition process (CVD), and a plurality of conductive layers are formed by a sputtering process to form wiring structures. The active region of each of the transistors is located inside the base substrate **101**.

[0109] FIG. 3B shows a cross-sectional schematic diagram of FIG. 3A along a section line I-I'. For clarity, some traces or electrode structures that are not directly connected are omitted in FIG. 3B. [0110] For example, as shown in FIG. 3B, the display substrate **10** includes a base substrate **101**, a first insulating layer **201**, a polysilicon layer **102**, a second insulating layer **202**, a first conductive layer **301**, a third insulating layer **203**, a second conductive layer **302**, a fourth insulating layer **204**, a third conductive layer **303**, a fifth insulating layer **205** and a fourth conductive layer **304** that are sequentially located on the base substrate **101**. In the following, the structure of the display substrate **10** will be described hierarchically, and FIG. 3B will be used as a reference and will be described together.

[0111] For clarity and convenience of description, FIG. 4A shows a portion of the display substrate **10** located below the first conductive layer **301**, that is, the base substrate **101** and the first insulating layer **201** and the polysilicon layer **102** on the base substrate **101**, including each of the transistors (P1, N1-N3), a storage capacitor Cst, and a resistance device **130**; FIG. 4B shows an enlarged schematic diagram of a sub-pixel **100** in FIG. 4A; for clarity, the section line I-I' in FIG. 3A is also correspondingly shown in FIG. 4A, FIGS. 5A to 5E show a formation process of the substrate structure shown in FIG. 4A.

[0112] As shown in FIG. 4B, for example, in a direction parallel to a plate surface of the base substrate **101**, the first data writing transistor P1 and the driving transistor N2 are on opposite sides of the storage capacitor Cst, for example, are on opposite sides of the storage capacitor Cst in the second direction D2.

[0113] With reference to FIG. 1C, this arrangement helps to increase a distance between the first data writing transistor P1 and the driving transistor N2, so that the resistance of the parasitic circuit is increased, and the risk of the failure of the CMOS circuit is further reduced.

[0114] For example, a material of the second capacitor electrode **142** of the storage capacitor **140** is a conductor or a semiconductor. For example, as shown in FIG. 3B and FIG. 4B, the second capacitor electrode **142** of the storage capacitor **140** is a first region **401** of the base substrate **101**; for example, the base substrate **101** is a P-type silicon-based substrate, and the material of the second capacitor electrode **142** is P-type monocrystal silicon. In a case that a voltage is applied to the first capacitor electrode **141**, the semiconductive first region **401** located under the first capacitor electrode **141** in the base substrate **101** forms an inversion region and becomes a conductor, so that the first region **401** is electrically connected with the contact hole regions (the contact hole regions **145a** and **145b** as shown in FIG. 4B) on both sides of the first region **401**. In this case, no additional doping process is performed on the first region **401**.

[0115] In another example, the first region **401** is, for example, a conductive region in the base substrate **101**, such as a heavily doped region, so that the second capacitor electrode **142** can obtain a stable and higher conductivity.

[0116] For example, the base substrate **101** further includes a second region **402**, and the second region **402** is an N-type well region in the base substrate **101**. As shown in FIG. 4B, for example, the first data writing transistor P1 and the resistance device **130** are arranged side by side in the second direction D2 in the second region **402**. Arranging the resistance device **130** made of polysilicon material in the N-type substrate helps to reduce parasitic effects, and improve the circuit characteristics.

[0117] For example, in a direction parallel to the plate surface of the base substrate **101**, the resistance device (R) **130** and the first data writing transistor P1 are located on a same side of the second capacitor electrode **142**. For example, in a direction parallel to the surface of the base substrate **101**, the driving transistor N2 and the bias transistor N3 are located on a same side of the second capacitor electrode **142**.

[0118] For example, as shown in FIG. 4B, the first data writing transistor P1 and the second data writing transistor P1 are arranged side by side in the first direction D1, and are symmetrical about a symmetry axis along the second direction D2. For example, the gate electrode **160** of the first data

writing transistor **P1** and the gate electrode **170** of the second data writing transistor **N1** are arranged side by side in the first direction **D1**, and are symmetrical about the symmetry axis along the second direction **D2**.

[0119] For example, the resistance device **130** is a U-shaped structure, such as an asymmetrical U-shaped structure, for example, lengths of two branches of the U-shaped structure are not equal. For example, as shown in FIG. **4B**, the second terminal **132** of the resistance device **130** is closer to the driving transistor **N2**.

[0120] The resistance device **130** arranged as a U-shaped structure helps to save a layout area occupied by the resistance device, so that the space utilization of the layout is improved, which helps to improve a resolution of the display substrate. For example, in a same space, the resistance device with the U-shaped structure can increase the length of the resistance device, so that a desired resistance value is obtained.

[0121] In addition, a design of the resistance device **130** as an asymmetric structure is also to make a reasonable use of the layout space. For example, as shown in FIG. **4B**, a contact hole region **411a** is designed above a shorter branch of the U-shaped resistor. The contact hole region **411a** is side by side with the second terminal **132** of the resistance device **130** in the first direction **D1**. For example, the contact hole region **411a** is an N-type heavily doped region (N+). For example, the contact hole region **411** is used to bias the well region **401** where the first data writing transistor **P1** is located, so that a threshold voltage change caused by parasitic effects such as a substrate bias effect is avoided, and the stability of the circuit is improved. For example, referring to FIG. **3B**, by applying a low-voltage bias to the P-type substrate **101** and a high-voltage bias to the N-type well region **402**, the parasitic PN junction between the P-type substrate **101** and the N-type well region **402** can be reversely biased, so that electrical isolate between devices is realized, the parasitic effect between the devices is reduced, and the stability of the circuit is improved.

[0122] For example, an opening of the U-shaped structure faces the first capacitor electrode **141**, the first terminal **131** and the second terminal **132** of the resistance device **130** are respectively located at two ends of the U-shaped structure. As shown in the figure, the first terminal **131** of the resistance device **130** is provided with a contact hole region **133** for electrically connecting with the gate electrode **150** of the driving transistor **N2**; the second terminal **132** of the resistance device **130** is provided with a contact hole region **134** for electrical connection with the first electrode **121** of the light-emitting element **120**.

[0123] For example, the material of the resistance device **130** includes polysilicon material, the contact hole regions **133** and **134** are doped regions for reducing contact resistance; a body region of the resistance device **130** other than the contact hole region is, for example, an intrinsic region or a low-doped region, so that a desired resistance value is obtained.

[0124] For example, the first capacitor electrode **141** of the storage capacitor **140** and the resistance device **130** are arranged in a same layer and insulated from each other, and both include a polysilicon material; and a doping concentration of the first capacitor electrode **141** of the storage capacitor **140** is higher than a doping concentration of the body region of the resistance device **130**. For example, the body region of the resistance device **130** is an intrinsic polysilicon material.

[0125] For example, the gate electrodes **160**, **170**, **150**, and **180** of the transistors **P1**, **N1** to **N3** and the first capacitor electrode **141** of the storage capacitor **140** are arranged in a same layer, and all include a polysilicon material. For example, as shown in FIG. **4B**, the gate electrode **150** of the driving transistor **N2** and the first capacitor electrode **141** are connected with each other as an integral structure.

[0126] FIG. **4B** also shows active regions **P1a**, **N1a**, **N2a**, and **N3a** of the transistors **P1**, **N1** to **N3**, respectively, and shows a first electrode **161** and a second electrode **162** of the first data writing transistor **P1**, a first electrode **171** and a second electrode **172** of the second data writing transistor **N1**, a first electrode **151** and a second electrode of the driving transistor **N2**, a first electrode **181** and a second electrode **182** of the bias transistor **N3**.

[0127] FIG. 4B also shows a gate contact region **165**, a first contact region **163**, and a second electrode contact region **164** of the first data writing transistor **P1**, a gate contact region **175**, a first contact region **173**, and a second electrode contact region **174** of the second data writing transistor **N1**, a gate contact region **155**, a first contact region **153** and a second electrode contact region **154** of the driving transistor **N2**, and a gate contact region **185**, a first contact region **183**, and a second electrode contact region **184** of the bias transistor **N3**. For example, each of the first electrode contact regions is a region where the corresponding first electrode is used to form electrical contacts, each of the second electrode contact regions is a region where the corresponding second electrode contact region is used to form electrical contacts, and each of the gate contact region is an area where the corresponding gate electrode is used to form electrical contacts.

[0128] For example, the active region **P1a** of the first data writing transistor **P1** and the active region **N1a** of the second data writing transistor **N1** are arranged side by side in the first direction **D1**, and are symmetrical about a symmetry axis along the second direction **D2**.

[0129] As shown in FIG. 4B, an area of the active region **N2a** of the driving transistor **N2** is larger than an area of other transistors, so that a greater width to length ratio can be obtained, which helps to improve the driving capability of the driving transistor **N2** and improve the display effect.

[0130] As shown in FIG. 4B, for the transistor with a larger active region, such as the drive transistor **N2** and the bias transistor **N3**, since the space is enough, at least two contact hole regions can be respectively provided on the first electrode and the second electrode of the drive transistor **N2** and the bias transistor **N3**, So that the drive transistor **N2** and the bias transistor **N3** can get sufficient contact with the structure to be connected and form a parallel structure, thereby reducing the contact resistance.

[0131] FIG. 4B also shows a contact hole region **144** on the first capacitor electrode **141** and contact hole regions **145a** and **145b** that are configured to be electrically connected with the second capacitor electrode **142**. As shown in FIG. 4B, the first capacitor electrode **141** and the second capacitor electrode **142** are respectively arranged with at least two contact hole regions to reduce the contact resistance.

[0132] With reference to FIG. 4A, the transistors (including the shape and size of each transistor, etc.), the storage capacitors, and the resistance devices in two sub-pixels **100** adjacent in the first direction **D1** are symmetrical about a symmetry axis along the second direction **D2** respectively, that is, the corresponding structures in the two sub-pixels are respectively symmetrical about the symmetry axis along the second direction **D2**. The transistors in two sub-pixels **100** adjacent in the second direction **D2** is axially symmetrical with respect to a symmetry axis along the first direction.

[0133] The symmetrical arrangement can maximize a uniformity of process errors, so that a uniformity of the display substrate is improved. In addition, the symmetrical arrangement allows some structures in the substrate that are arranged in a same layer and are connected with each other to be integrally formed, compared with separate arrangements, the symmetrical arrangement can make the pixel layout more compact, and improves the space utilization, so that the resolution of the display substrate is improved.

[0134] For example, as shown in FIG. 4A, second regions **402** of two sub-pixels **100** adjacent in the first direction **D1** are in an integral structure, second regions **402** of two sub-pixels **100** adjacent in the second direction **D2** are in an integral structure, that is, the first data writing transistor **N1** and the resistance device **130** in the four adjacent sub-pixels **100** are located in a same well region. Compared with separate well regions, this arrangement can make the arrangement of pixels more compact under the premise of meeting the design rules, which helps to improve the resolution of the display substrate.

[0135] For example, as shown in FIG. 4A, the active regions **P1a** of the first data writing transistors **P1** of two sub-pixels adjacent in the second direction **D2** are connected with each other as an integral structure, that is, the active regions **P1a** of the two first data writing transistors **P1** are

located in a same doped region **A1** (P well) of the same second region **402**, and the first electrodes of the two first data transistors **P1** are connected with each other as an integral structure, to receive the same data signal **Vd**.

[0136] For example, as shown in FIG. **4A**, the active regions **N1a** of the second data writing transistors **N1** of two sub-pixels adjacent in the second direction **D2** are connected with each other as an integral structure, that is, the active regions **N1a** of the two second data writing transistors **N1** are located in a same doped region **A2** (N-well) of the base substrate **101**, and the first electrodes of the two second data writing transistors **N1** are connected with each other as an integral structure, to receive the same data signal **Vd**.

[0137] For example, as shown in FIG. **4A**, the gate electrodes of the first data writing transistor **P1** or the gate electrodes of the second data writing transistor **N2** of two sub-pixels **100** adjacent in the first direction **D1** are connected with each other to form an integral structure.

[0138] Since for each row of pixels, the gate electrodes of the first data writing transistor **P1** are all configured to receive the same first control signal **SEL**, and the gate electrodes of the second data writing transistor **N1** are all configured to receive the same second control signal **SEL_B**; additionally, since the transistors of the two sub-pixels adjacent in the first direction **D1** are mirror-symmetrical, and the case where the first data writing transistor **P1** of two sub-pixels are adjacent and the case where the second data writing transistors **N1** of two sub-pixels are adjacent happen alternately in the first direction **D1**; therefore, the gate electrodes of two adjacent first data writing transistors **P1** can be directly connected as an integral structure to form a first control electrode group **191**, and the gate electrodes of the adjacent second data writing transistors **N1** can be directly connected as an integral structure to form a second control electrode group **192**. This arrangement can make the arrangement of the pixels more compact on the premise of meeting the design rules, which helps to improve the resolution of the display substrate.

[0139] As shown in FIG. **4A**, for two sub-pixels **100** adjacent in the first direction **D1**, in a case that their driving transistors **N2** are adjacent to each other, the active regions **N2a** of the two driving transistors **N2** are connected with each other as an integral structure, that is, the active regions **N2a** of the two driving transistors **N2** are located in a same doped region **B** (N well) of the base substrate **101**, and the first electrodes of the two driving transistors **N2** are connected with each other as an integral structure to form a third control electrode group **193**, to receive the same first power supply voltage **VDD**; in a case that their bias transistors **N3** are adjacent to each other, the gate electrodes of the two bias transistors **N3** are connected to each other as an integral structure, to receive the same second common voltage **Vcom2**; the active regions **N3a** of the two bias transistors **N3** are connected with each other as an integral structure, that is, the active regions **N3a** of the two bias transistors **N3** are located in a same doped region **C** (N well) of the base substrate **101**, and the first electrodes of the two bias transistors **N3** are connected with each other to form an integral structure, to receive the same second power voltage **VSS**.

[0140] This arrangement can make the arrangement of the pixels more compact on the premise of meeting the design rules, which helps to improve the resolution of the display substrate.

[0141] FIGS. **5A** to **5D** show the formation process of the substrate structure shown in FIG. **4A**, for clarity, only two rows and two columns of sub-pixels are shown in the figure, that is, four adjacent sub-pixels **100** are shown, and the four sub-pixels **100** form a pixel unit group **420**. FIG. **4A** illustrates the pixel unit group **420** with a dotted box. For example, the display substrate comprises a plurality of pixel unit groups arranged along the first direction and the second direction.

[0142] In the following, a forming process of the display substrate provided by the embodiment of the present disclosure will be exemplarily described with reference to FIGS. **5A** to **5D**, but this is not a limitation of the present disclosure.

[0143] For example, a silicon-based substrate is provided, for example, a material of the silicon-based substrate is P-type monocrystalline silicon. N-type transistors (such as driving transistors) can be directly manufactured on the P-type silicon substrate, that is, the P-type substrate serves as

the channel region of the N-type transistors, which is conducive to taking advantage of a high speed of NMOS devices, and improves the circuit performance.

[0144] As shown in FIG. 5A, for example, N-type doping is performed on a P-type silicon substrate, to form an N-type well region, that is, the second region **402**, which serves as a substrate for the first data writing transistor **P1** and the resistance device **130**.

[0145] For example, the second regions **402** of two sub-pixels adjacent in the first direction **D1** may be connected with each other, and the second regions **402** of two sub-pixels adjacent in the second direction **D2** may be connected with each other. For example, the region which is not to be doped in the base substrate **101** is shielded while performing the N-type doping treatment.

[0146] As shown in FIG. 4B and FIG. 5B, for example, a first insulating layer **201** is formed on the base substrate **101**, then a polysilicon layer **102** is formed on the first insulating layer **201**.

[0147] The first insulating layer **201** includes the gate insulating layer of each of the transistors, and further includes a dielectric layer **104** of the storage capacitor Cst. The polysilicon layer **102** includes a first capacitor electrode **141**, a resistance device **130**, and gate electrodes **150**, **160**, **170**, and **180** of each of the transistors (**P1**, **N1** to **N3**).

[0148] The gate electrode of the first data writing transistor **P1** is located in the second region **402**, and the N-type well region serves as the channel region of the P-type transistor. The resistance device **130** is also located in the second region **402**, that is, an orthographic projection of the resistance device **130** on the base substrate is in the second region **4**. Forming the resistance device **130** made of polysilicon material in the N-type substrate helps to reduce parasitic effects and improve the circuit characteristics. Each of the N-type transistors is directly formed on the P-type substrate outside the N-type well region.

[0149] For example, as shown in FIG. 5B, the orthographic projections of the first capacitor electrodes **141** of the four sub-pixels in each pixel unit group on the base substrate is outside the second region **402**, and surrounds the second region **402**. For example, the second region **402** is rectangular, the orthographic projection of the first capacitor electrode **141** of each sub-pixel on the base substrate is around a corner of the rectangle; for example, each first capacitor electrode **141** comprises a concave structure, and an outline of the concave structure is L-shaped, the corner of the rectangle stretches into the orthographic projection of the concave structure and matches the L-shaped outline.

[0150] As shown in FIG. 5B, patterns of the polysilicon layers in the two sub-pixels adjacent in the first direction **D1** are symmetrical about a symmetry axis along the second direction **D2**; and patterns of the polysilicon layers in the two sub-pixels adjacent in the second direction **D2** are symmetrical about a symmetry axis along the first direction **D1**; that is, the pattern of the polysilicon layer is a symmetrical pattern. For example, as shown in FIG. 5B, the resistance devices of sub-pixels adjacent in the first direction are symmetrical about a symmetry axis along the second direction, and the resistance devices of sub-pixels adjacent in the second direction are symmetrical about a symmetry axis along the first direction. For example, the first capacitor electrodes of sub-pixels adjacent in the first direction are symmetrical about a symmetry axis along the second direction, and the first capacitor electrodes of sub-pixels adjacent in the second direction are symmetrical about a symmetry axis along the first direction.

[0151] For example, the gate electrodes of the first data writing transistor **P1** of two sub-pixels adjacent in the first direction **D1** are symmetrical about a symmetry axis along the second direction, and the gate electrodes of the second data writing transistor **N1** of the two sub-pixels adjacent in the first direction **D1** are symmetrical about a symmetry axis along the second direction. For example, the gate electrodes of the first data writing transistor **P1** of two sub-pixels adjacent in the first direction **D1** are integrally formed, and the gate electrodes of the second data writing transistor **N1** of the two sub-pixels adjacent in the first direction **D1** are integrally formed.

[0152] For example, the gate electrodes of the first data writing transistor **P1** of two sub-pixels adjacent in the second direction **D2** are symmetrical about a symmetry axis along the first direction,

and the gate electrodes of the second data writing transistor N1 of the two sub-pixels adjacent in the second direction D2 are symmetrical about a symmetry axis along the first direction.

[0153] For example, the first insulating layer is formed on the base substrate by a thermal oxidation method. For example, a material of the first insulating layer is silicon nitride, oxide or oxynitride.

[0154] For example, a polysilicon material layer is formed on the first insulating layer by a chemical vapor deposition process (PVD), then a photolithography process is performed on the polysilicon material layer to form the polysilicon layer **102**.

[0155] FIG. 5C shows a doping window region **103** of the base substrate (left picture), and also shows the doping window region on the substrate structure as shown in FIG. 5B (right picture). For example, the doping is heavy doping, to form contact hole regions for electrical connection in the base substrate. For example, the doping window region includes the source region and the drain region of each of the transistors. For example, the doping window region also includes the contact hole regions of the substrate and the contact hole regions of the resistance device **130**, for example, including the contact hole regions **400a**, **400b**, **411a**, **411b**, **145a**, **145b**, **133**, **134** shown in FIG. 4B. For example, since the gate electrode of the transistor is formed of polysilicon material, the polysilicon gate electrode also needs to be doped. In a case that the doping is performed, a barrier layer needs to be formed to cover the non-doped region, and only the corresponding doping window region and amorphous silicon areas are exposed.

[0156] It should be noted that FIG. 5C only illustrates each doping window region, in a case that an actual doping process is performed, a corresponding barrier layer/mask layer can be arranged to expose both the corresponding doping window region and the polysilicon region for doping. For example, a material of the barrier layer/mask layer may be photoresist or an oxide material.

[0157] As shown in FIG. 5D, a barrier layer **135** is formed corresponding to the resistance device **130**. In order to protect a resistance of the resistance device **130**, the resistance device **130** needs to be shielded during the doping process to prevent the resistance device **130** from being damaged due to the doping. The barrier layer **135** covers the main body of the resistance device **130** and only exposes the contact hole regions **133** and **134** at both ends of the resistance device **130**.

[0158] For example, the barrier layer **135** may be made of silicon nitride, oxide or oxynitride, or a photoresist material. After finishing the doping process, the barrier layer **135** may remain in the display substrate, or may be removed.

[0159] In other examples, the barrier layer **135** of the resistance device **130** can also be formed together with barrier layers/mask layers in other regions during doping, which are not limited in the embodiments of the present disclosure.

[0160] For example, during the doping process, the N-type doping and the P-type doping need to be performed separately, for example, to form both the source region and the drain region of the N-type transistor and both the source region and the drain region of the P-type transistor. In a case that the N-type doping process is performed, the barrier layer needs to be formed to shield the region where the N-type doping is not to be performed; in a case that the P-type doping process is performed, a barrier layer needs to be formed to shield the region where the P-type doping is not to be performed.

[0161] FIG. 5E shows the N-type doped region SN and the P-type doped region SP with different shading patterns (left picture), and also shows the N-type doped region SN and the P-type doped region SP on the substrate shown in FIG. 5D (right picture). The N-type doped region SN and the P-type doped region SP are also shown in FIG. 4B, and can be referred to together.

[0162] For example, performing an N-type doping process includes forming a barrier layer to cover the P-type doped region SP, and to cover the region of the N-type doped region SN except for the doping window region and the polysilicon region, and only the doping window region and the polysilicon region in the N-type doped region SN are retained, that is, the SN region overlaps with the doping window region **103** and the polysilicon region shown in FIG. 5C; then an N-type doping process is performed. Referring to FIG. 4B, the gate electrodes, the first electrodes and the second

electrodes of the transistors **N1** to **N3**, and the contact hole regions **411a**, **411b**, **145a**, **145b** can be formed through the N-type doping process. The N-type doping process may be, for example, an ion implantation process, and the doping element may be, for example, boron element.

[0163] For example, performing a P-type doping process includes forming a barrier layer to cover the N-type doped region **SN**, and to cover the P-type doped region **SP** except for the doping window region and the polysilicon region, and only the doping window region and the polysilicon region in the P-type doped region **SP** are retained, that is, the **SP** region overlaps with the doping window region **103** and the polysilicon region shown in FIG. 5C; then the P-type doping process is performed. Referring to **4B**, the gate electrode, the first electrode and the second electrode of the transistor **P1**, and the contact holes **400a**, **400b**, **133**, and **134** can be formed through the P-type doping process. The P-type doping process may be, for example, an ion implantation process, and the doping element may be, for example, phosphorus element.

[0164] In the doping process, for example, an ion implantation process is applied, and the polysilicon pattern can serve as a mask, so that an implantation of ions into the silicon-based substrate happens on both sides of the polysilicon, thereby forming the first electrode and the second electrode of each of the transistors, and realizing a self-alignment. In addition, a resistivity of the polysilicon with original high resistance is reduced through the doping process, the gate electrode of each transistor and the first capacitor electrode can be formed. Therefore, using the polysilicon material the material of the resistance device and the gate electrode has multiple beneficial effects, and the process cost is reduced.

[0165] In this way, the structure of the display substrate shown in FIG. 4A is formed, which includes each of the transistors **P1**, **N1** to **N3**, the resistance device **130** and the storage capacitor **Cst**.

[0166] For example, corresponding transistors, the resistance devices, and the storage capacitors **Cst** in two sub-pixels adjacent in the first direction **D1** are respectively symmetrical about a symmetry axis along the second direction **D2**; corresponding transistors, resistance devices, and storage capacitors **Cst** in two sub-pixels in adjacent the second direction **D2** are respectively symmetrical about a symmetry axis along the first direction **D1**.

[0167] It should be noted that, in the embodiment, the storage capacitor **Cst** is a capacitor formed by a field effect, after a voltage is applied to the first capacitor electrode **141**, inversion charges are generated in a region of the base substrate **101** under the first capacitor electrode **141**, rendering a bottom electrode plate of the storage capacitor **Cst**, i. e. the second capacitor electrode **142** conductive.

[0168] In other embodiments, a conducting treatment (for example, a doping treatment) may be performed in advance on the region of the base substrate **101** located below the first capacitor electrode **141** to form the second capacitor electrode **142**. The embodiments of the present disclosure are not limited thereto.

[0169] The second insulating layer **202**, the first conductive layer **301**, the third insulating layer **203**, the second conductive layer **302**, the fourth insulating layer **204**, the third conductive layer **303**, the fifth insulating layer **205**, and the fourth conductive layer **304** are sequentially formed on the substrate shown in FIG. 4A, and the display substrate shown in FIG. 3A is formed.

[0170] FIGS. 6A and 6B respectively show a pattern of the first conductive layer **301** and a situation where the first conductive layer **301** is arranged on the substrate structure shown in FIG. 4A, FIG. 6C shows a cross-sectional schematic diagram of FIG. 6B along a section line IV-IV'; FIG. 6B also shows via holes in the second insulating layer **202**, and the via holes correspond to the contact regions in FIG. 4B in a one-to-one correspondence and are used to electrically connect each of the contact hole regions with the pattern in the first conductive layer **301**. For clarity, only two rows and six columns of sub-pixels are shown in the figure, and a dotted frame is used to show a region of one sub-pixel **100**; in addition, FIG. 6B also correspondingly shows a position of the section line I-I' in FIG. 3A.

[0171] As shown in FIG. 6A, patterns of the first conductive layers in two sub-pixels adjacent in the first direction D1 are symmetrical about a symmetry axis along the second direction D2; patterns of the first conductive layers in two sub-pixels adjacent in the second direction D2 are symmetrical about a symmetry axis along the first direction D1. The pattern of the first conductive layer will be exemplarily described below by taking one sub-pixel as an example.

[0172] As shown in FIG. 6A, the first conductive layer **301** includes a connection electrode **313** (an example of the second connection electrode of the present disclosure), and the connection electrode **313** is used to electrically connect the first terminal **131** of the resistance device **130** with the second electrode **152** of the driving sub-circuit **112**.

[0173] For example, with reference to FIG. 6B, a first end of the connection electrode **313** is electrically connected with the first terminal **131** of the resistance device **130** through a via hole **225** (an example of the first via hole of the present disclosure) in the second insulating layer **202**; a second end of the connection electrode **313** includes a first branch **331** and a second branch **332**, combining with FIG. 3B, the first branch **331** is electrically connected with the first electrode **151** of the driving transistor N2 through the via hole **226a** (an example of the second via hole of the present disclosure) in the second insulating layer **202**, and the second branch **332** is electrically connected with the first electrode **181** of the bias transistor N3 through a via hole **226b** in the second insulating layer **202**.

[0174] For example, as shown in FIG. 6B, in the second direction D2, the via hole **225** and the via hole **226a** are respectively located on opposite sides of the first capacitor electrode **141**; that is, an orthographic projection of the connection electrode **313** on the base substrate **101** crosses over an orthographic projection of the first capacitor electrode **141** on the base substrate **101** in the second direction D2.

[0175] For example, a number of both the via hole **226a** and the via hole **226b** may be at least two, to reduce the contact resistance.

[0176] For example, with referring to FIGS. 6A and 6B, the first conductive layer **301** further includes a connection electrode **314**, the connection electrode **314** is electrically connected with the second terminal **132** of the resistance device **130** through the via hole **229** in the second insulating layer **202**, and the connection electrode **314** is configured to be electrically connected with the first electrode **121** of the light-emitting element **120**.

[0177] For example, the connection electrode **314** is L-shaped, one branch of the connection electrode **314** is electrically connected with the second terminal **132** of the resistance device **130**, and the other branch is configured to be electrically connected with the first electrode **121** of the light-emitting element **120**.

[0178] For example, as shown in FIG. 6B and FIG. 6C, the first conductive layer **301** also includes a third capacitor electrode **315**, the third capacitor electrode **315** overlaps with the first capacitor electrode **141** in a direction perpendicular to the base substrate. The third capacitor electrode **315** is on a side of the first capacitor electrode **141** away from the second capacitor electrode **142**, and is configured to be electrically connected with the second capacitor electrode **142**; that is, in the direction perpendicular to the base substrate, the second capacitor electrode **142** and the third capacitor electrode **315** are located on two sides of the first capacitor electrode **141** respectively, and are electrically connected with each other, so that a structure of parallel capacitors is formed, and the capacitance value of the storage capacitor Cst is increased.

[0179] For example, as shown in FIG. 6B and FIG. 6C, the third capacitor electrode **315** comprises a first portion **315a** and a second portion **315b**, and the first portion **315a** and the second portion **315b** are spaced apart from each other in the first direction D1. For example, the first portion **315a** is electrically connected with the contact hole region **145b** through a via hole **228** in the second insulating layer **202**, so as to be electrically connected with the second capacitor electrode **142**; the second portion **315b** is electrically connected with the contact hole region **145a** through a via hole **227** in the second insulating layer **202**, so as to be electrically connected with the second capacitor

electrode **142**.

[0180] For example, the first portion **315a** and the second portion **315b** of the third capacitor electrode **315** are located on two sides of the connection electrode **313** in the first direction **D1**, and are respectively spaced apart from the connection electrode **313**.

[0181] For example, the third capacitor electrodes of two sub-pixels adjacent in the first direction **D1** are about a symmetry axis along the second direction **D2**; and the third capacitor electrodes of two sub-pixels adjacent in the second direction **D1** are about a symmetry axis along the first direction **D1**.

[0182] For example, as shown in FIG. **6B**, the first portions **315a** or the second portions **315b** of the third capacitor electrodes of two sub-pixels adjacent in the first direction **D1** are in an integral structure.

[0183] For example, as shown in FIG. **6B**, for each pixel unit group **420**, the first portions **315a** of the third capacitor electrodes of two sub-pixels adjacent in the first direction **D1** are connected with each other as an integral structure.

[0184] For example, as shown in FIG. **6B**, the second portion **315b** of the third capacitor electrode **315** of a sub-pixel in each pixel unit group **420** and the second portion **315b** of the third capacitor electrode **315** of a sub-pixel, which is adjacent to the sub-pixel, in a pixel unit group adjacent to the each pixel unit group **420** are connected as an integral structure.

[0185] For example, as shown in FIG. **6A**, adjacent third capacitor electrodes **315** in two sub-pixels adjacent in the first direction **D1** may be integrally formed to receive the same second power voltage **VSS**, and adjacent third capacitor electrodes **315** in two sub-pixels adjacent in the first direction **D1** may be integrally formed to receive the same second power voltage **VSS**.

[0186] For example, at least two via holes **227** and **228** may be arranged respectively to reduce the contact resistance; for example, the at least two via holes **227** are arranged along the second direction **D2**, and the at least two via holes **228** are arranged along the second direction **D2**.

[0187] For example, the first conductive layer **301** further includes a connection electrode **317** (an example of the first connection electrode of the present disclosure), and the connection electrode **317** is used to electrically connect the second terminal of the data writing sub-circuit with the first terminal of the storage sub-circuit, that is, electrically connecting the second electrode **161** of the first data writing transistor **P1**, the second electrode **171** of the second data writing transistor **N1**, and the first capacitor electrode **141**.

[0188] With referring to FIG. **6A** and FIG. **6B**, the connection electrode **317** includes three ends, for example, a T-shaped structure. With referring to FIG. **3B**, the first end of the connection electrode **317** is electrically connected with the second electrode of the first data writing transistor **P1** through a via hole **261a** in the second insulating layer **202**, the second end of the connection electrode **317** is electrically connected with the second electrode of the second data writing transistor **N1** through a via hole **261b** in the second insulating layer **202**, and the third end of the connection electrode **317** is electrically connected with the first capacitor electrode **141** through a via hole **261c** in the second insulating layer **202**.

[0189] For example, as shown in FIG. **6B**, in the second direction **D2**, the third end of the connection electrode **314** at least partially overlaps with the connection electrode **317**. This arrangement makes the pixel layout more compact, so that the space utilization rate of the display substrate is improved, and the resolution of the display substrate is improved.

[0190] With referring to FIG. **6A** and FIG. **6B**, the first conductive layer **301** further includes a first scan line connection portion **311** and a second scan line connection portion **312**, and the first scan line connection portion **311** is configured to be electrically connected with the first scan line so that the gate electrode of the first data writing transistor **P1** receives the first control signal **SEL**. The second scan line connection portion **312** is configured to be electrically connected with the second scan line so that the gate electrode of the second data writing transistor **N1** receives the first control signal **SEL_B**.

[0191] For example, the first scan line connection portion **311** is electrically connected with the gate electrode of the first data writing transistor **P1** through a via hole **221** in the second insulating layer **202**, and the second scan line connection portion **312** is electrically connected with the gate electrode of the second data writing transistor **N1** through a via hole **222** in the second insulating layer **202**.

[0192] For example, as shown in FIG. **6A**, sub-pixels adjacent in the first direction **D1** share a first scan line connection portion **311** or a second scan line connection portion **312**.

[0193] For the specific description of the first scan line connection portion and the second scan line connection portion, the description of FIGS. **10A** to **10B** below can be referred to.

[0194] As shown in FIG. **6A**, the first conductive layer **301** further includes a data line connection portion **245**, and the data line connection portion **245** is configured to be electrically connected with the data line, so that the first electrode of the first data writing transistor **P1** and the first electrode of the second data writing transistor **N1** receive the data signal **Vd** transmitted by the data line.

[0195] As shown in FIG. **6B**, the data line connection portion **245** is electrically connected with the first electrode **161** of the first data writing transistor **P1** through a via hole **223** in the second insulating layer **202**, and the data line connection portion **245** is electrically connected with the first electrode **171** of the second data writing transistor **N1** through a via hole **224** in the second insulating layer **202**.

[0196] For example, as shown in FIG. **6A**, a plurality of data line connection portions **245** are arranged at intervals in the first direction **D1**, for example, located at a boundary of two sub-pixel rows. For example, two sub-pixels adjacent in the second direction **D2** share one data line connection portion **245**.

[0197] For the specific description of the data line connection portion, the description of the second data line connection portion in FIGS. **8A** to **8D** below can be referred to.

[0198] Referring to FIGS. **6A** and **6B**, the first conductive layer **301** further includes a connection electrode **318**, and the connection electrode **318** is electrically connected with the first electrode of the driving transistor **N2** through a via hole **230** in the second insulating layer **202**.

[0199] Referring to FIGS. **4A** and **6B**, the first conductive layer **301** further includes connection electrodes **319a**, **319b**, **319c**, these connection electrodes are all arranged for biasing the substrates of the transistors, for example, used for connecting the N-type substrate to a first power voltage terminal to receive the first power voltage **VDD** (high voltage), or used for connecting the P-type substrate to a second power voltage terminal to receive the second power supply voltage **VSS** (low voltage), as a result, parasitic effects such as the substrate bias effect can be avoided, and the stability of the circuit can be improved.

[0200] With referring to FIG. **4B**, the connection electrodes **319a** and **319b** are respectively electrically connected with the contact hole regions **411a** and **411b** in the second region (N-well region) **402** of the base substrate **101** through via holes **262a** and **262b** in the second insulating layer **202**, the connection electrodes **319a** and **319b** are configured to be electrically connected with the first voltage terminal **VDD** to bias the N-type substrate of the first data writing transistor **P1**. The connection electrode **319c** is electrically connected with the contact hole region **400a** in the base substrate **101** through a via hole **262c** in the second insulating layer **202**, and the connection electrode **319c** is configured to be electrically connected with the second voltage terminal **VSS** to bias the P-type substrate where the second data writing transistor **N1** is located.

[0201] With referring to FIGS. **6A** to **6B**, the first conductive layer **301** further includes a bias voltage line **250**, the bias voltage line **250** is extended along the first direction **D1**, and is electrically connected with the gate electrode of the bias transistor **N3** through a via hole **263** in the second insulating layer **202**, to provide the second common voltage **Vcom2**.

[0202] With reference to FIGS. **4B** and **6A** to **6B**, the first conductive layer **301** further includes a power line **260**, the power line **260** is extended along the first direction **D1** and is used for

transmitting the second power voltage VSS. The power line **260** is electrically connected with the first electrode of the bias transistor N3 through a via hole **264a** in the second insulating layer **202** to provide the second power voltage VSS, and is electrically connected with a contact hole region **400b** in the base substrate **101** through a via hole **264b** in the second insulating layer **202** to bias the P-type substrate where the second data writing transistor N1 is located.

[0203] FIG. 7A shows a schematic diagram of the second conductive layer **302**, FIG. 7B shows the second conductive layer **302** on the basis of the first conductive layer **301**, FIG. 7B further shows the via hole in the third insulating layer **203**, and the via hole in the third insulating layer **203** is used to connect the pattern in the first conductive layer **301** and the pattern in the second conductive layer **302**. For clarity, only four rows and six columns of sub-pixels are shown in the figure, a dividing line of two sub-pixel rows is further shown by a dotted line; in addition, FIG. 7B also correspondingly shows a position of the section line I-I' in FIG. 3A.

[0204] As shown in FIG. 7A, patterns of second conductive layers in two sub-pixels adjacent in the first direction D1 are symmetrical about a symmetry axis along the second direction D2; and patterns of second conductive layers in two sub-pixels adjacent in the second direction D2 are symmetrical about a symmetry axis along the first direction D1. The patterns of the second conductive layers will be exemplarily described below by taking one sub-pixel as an example.

[0205] As shown in FIG. 7A, the second conductive layer **302** includes power lines **270a**, **270b**, **280a**, and **280b** extended along the first direction D1, the power lines **270a** and **270b** are used to transmit the second power voltage VSS, and the power lines **280a** and **280b** are used to transmit the first power voltage VDD. The power lines **270a**, **280a**, **270b**, and **280b** are alternately arranged one by one in the second direction D2.

[0206] With reference to FIGS. 3B, 7A, and 7B, the power line **270a** is electrically connected with the power line **260** in the first conductive layer **301** through a plurality of via holes **235** in the third insulating layer **203**, so that a parallel structure is formed, the resistance of the wiring is effectively reduced; the plurality of via holes **235** are arranged along the first direction D1. For example, the power line **270b** is electrically connected with the third capacitor electrode **315** through via holes **236** in the third insulating layer **203** to provide the second power voltage VSS; for example, the plurality of via holes **236** are arranged along the second direction D2. For example, the power line **270b** is also electrically connected with the third capacitor electrode **315** (**315b**) through via holes **267** in the third insulating layer **203** to provide the second power voltage VSS; for example, the plurality of via holes **267** are arranged along the second direction D2.

[0207] For example, in the second direction D2, a width of the power line **270b** is greater than a width of the power line **270a**, this is because the first portion and the second portion of the third capacitor electrode **315** that is electrically connected with the power line **270b** both have a larger area, setting the power line **270b** to have a larger width can facilitate the formation of a plurality of connection holes **236** and **267** with the third capacitor electrode **315**, so that the contact resistance is effectively reduced.

[0208] With reference to FIGS. 7A and 7B, the power line **280a** is electrically connected with the connection electrode **318** in the first conductive layer **301** through a via hole **237** in the third insulating layer **203**, so that the power line **280a** is connected with the first electrode of the driving transistor N2 to provide the first power supply voltage VDD. The power line **280b** is electrically connected with the connection electrode **319a** in the first conductive layer **301** through a via hole **238** in the third insulating layer **203**, so that the second region (N-well region) **402** in the base substrate **101** is biased with a high voltage; for example, the plurality of via holes **238** are arranged along the second direction D2.

[0209] For example, in the second direction D2, a width of the power line **280b** is greater than a width of the power line **280a**, this is because the connection electrode **319a** electrically connected to the power line **280b** has a larger size in the second direction D2, setting the power line **280b** to have a larger width can facilitate the formation of a plurality of connection holes **238** between the

power line **280b** and the connection electrode **319a**, so that the contact region with the connection electrode **319a** is increased, and the contact resistance is effectively reduced.

[0210] For example, the second conductive layer **302** further includes a plurality of first scan lines **210** and a plurality of second scan lines **220** extended along the first direction **D1**. For example, the scan line **11** shown in FIG. **1A** may be the first scan line **210** or the second scan line **220**.

[0211] With reference to FIG. **6A** and FIG. **6B**, the first scan line **210** is electrically connected with the first scan line connection portion **311** through a via hole **231** in the third insulating layer **203**, and the second scan line **220** is electrically connected with the second scan line connection portion **312** through a via hole **232** in the third insulating layer **203**.

[0212] For the specific description of the first scan line and the second scan line, the description of FIGS. **10A-10B** below may be referred to.

[0213] For example, with referring to FIG. **3B**, FIG. **7A** and FIG. **7B**, the second conductive layer **302** further includes a connection electrode **323**, and the connection electrode **323** is electrically connected with the connection electrode **314** in the first conductive layer **301** through a via hole **239** in the third insulating layer **203**, so that the connection electrode **323** is connected to the second terminal **132** of the resistance device **130**. The connection electrode **323** is configured to be electrically connected with the first electrode **121** of the light-emitting element **120**. For example, the number of the via hole **239** is at least two.

[0214] For example, with referring to FIG. **7A** and FIG. **7B**, the second conductive layer **302** further includes a connection electrode **324**, and the connection electrode **324** is electrically connected with the connection electrode **319b** in the first conductive layer **301** through a via hole **265** in the third insulating layer **203**, so that the connection electrode **324** is electrically connected with the contact hole region **411b** in the second region (N-well region) **402** in the base substrate **101**.

[0215] For example, with referring to FIG. **7A** and FIG. **7B**, the second conductive layer **302** further includes a connection electrode **325**, the connection electrode **325** is electrically connected with the connection electrode **319c** in the first conductive layer **301** through a via hole **266** in the third insulating layer **203**, so that the connection electrode **325** is electrically connected with the contact hole region **400a** in the base substrate **101**.

[0216] For example, the connection electrode **325** is in a cross-shaped structure. For example, the connection electrodes **324** and the connection electrodes **325** are alternately distributed in the first direction **D1**, and are located at a boundary of two sub-pixel rows.

[0217] For example, as shown in FIG. **7A**, the second conductive layer **302** further includes a data line connection portion **244**. With referring to FIG. **7B**, the data line connection portion **244** is electrically connected with the data line connection portion **245** in the first conductive layer **301** through a via hole **233**.

[0218] For example, as shown in FIG. **7A**, a plurality of data line connection portions **244** are arranged at intervals in the first direction **D1**, and a connection electrode **324** or a connection electrode **325** is provided between every two adjacent data line connection portions **244**.

[0219] For example, the data line connection portion **244** is located at a boundary between two sub-pixel rows. For example, two sub-pixels adjacent in the second direction **D2** share one data line connection portion **244**.

[0220] For example, with referring to FIGS. **7A** and **7B**, in the second direction **D2**, the data line connection portions **244** located in each column of sub-pixels are alternately located on two sides of the data line connection portions **245**, and are electrically connected with the first end and the second end of the data line connection portions **245** through via holes **233** and **234**, respectively, which is to connect the data line connection portions **245** to different data lines.

[0221] For a specific description of the data line connection portion, the description of the first data line connection portion in FIGS. **11A** to **11D** below may be referred to.

[0222] FIG. **8A** shows a schematic diagram of the third conductive layer **303**, FIG. **8B** shows the

third conductive layer **303** on the basis of the second conductive layer **302**, FIG. **8B** also shows the via holes in the fourth insulating layer **204**, and the via holes in the fourth insulating layer **204** is used to connect the pattern in the second conductive layer **302** with the pattern in the third conductive layer **303**. For clarity, the figures only show the conductive patterns corresponding to the sub-pixels in four rows and six columns, and a dividing line of two rows of sub-pixels is shown in FIG. **8A** with a dashed line; in addition, FIG. **8B** also correspondingly shows the position of the section line I-I' in FIG. **3A**.

[0223] For example, the third conductive layer **303** includes a plurality of data lines extended along the second direction **D2**, and the data line is configured to be connected with the first terminal of the data writing sub-circuit in the sub-pixel to provide the data signal **Vd**. For example, as shown in FIG. **8A**, the plurality of data lines include a plurality of first data lines **241** and a plurality of second data lines **242**, the first data lines **241** and the second data lines **242** are alternately arranged one by one along the first direction **D1**. For example, the data line **12** shown in FIG. **1A** may be the first data line **241** or the second data line **242**.

[0224] For example, the data line is divided into a plurality of data line groups, each of the data line groups includes a first data line **241** and a second data line **242**. For example, each sub-pixel column is correspondingly connected with a data line group, that is, with a first data line **241** and a second data line **242**; that is, one column of sub-pixels is driven by two data lines. This helps to reduce the load on each data line, so that the driving ability of the data line is improved, the signal delay is reduced, and the display effect is improved.

[0225] Referring to FIG. **8B**, the first data line **241** is electrically connected with the data line connection portion **244** which is between the first row of sub-pixels and the second row of sub-pixels and in the second conductive layer **302** shown in FIG. **7B** through a via hole **403** in the fourth insulating layer **204**, so as to provide the data signal to the first and second rows of sub-pixels; the second data line **242** is electrically connected with the data line connection portion **244** which is between the third row of sub-pixels and the fourth row of sub-pixels and in the second conductive layer **302** shown in FIG. **7B** through a via hole **404** in the fourth insulating layer **204**, so as to provide the data signal to the third and fourth rows of sub-pixels.

[0226] For the specific description of the first data line and the second data line, the descriptions in FIGS. **11A-11D** below may be referred to. For the convenience of comparison, FIG. **8B** shows the positions corresponding to the section lines II-II' and III-III' in FIG. **11B**.

[0227] For example, the third conductive layer **303** includes power lines **330** and **340** extended along the second direction **D2**. The power line **330** is configured to transmit the first power voltage **VDD**, and the power line **340** is configured to transmit the second power voltage **VSS**. As shown in FIG. **8A**, the power line **330** and the power line **340** are alternately arranged one by one in the first direction **D1**.

[0228] Referring to FIG. **8B**, the power line **330** is electrically connected with the power lines **280a** and **280b** in the second conductive layer **302** through via holes **405** and **406** in the fourth insulating layer **204**, respectively, so that a meshed power line structure for transmitting the first power voltage is formed. This structure helps to reduce the resistance on the power line, so that the voltage drop on the power line is reduced, which helps to evenly deliver the first power voltage **VDD** to each of the sub-pixels of the display substrate. The power line **330** is also electrically connected with the connection electrode **324** (referring to FIG. **7A**) in the second conductive layer **302** through a via hole **407** in the fourth insulating layer, so that the power line **330** is electrically connected with the contact hole region **411b** in the second region **402** (N-well region) in the base substrate **101**, to bias the N-type substrate where the first data writing transistor **P1** and the resistance device **130** are located.

[0229] Referring to FIG. **8B**, the power line **340** is electrically connected with the power lines **270a** and **270b** in the second conductive layer **302** through a via hole **408** and a via hole **409** in the fourth insulating layer **204**, respectively, so that a meshed power line structure for transmitting the second

power supply voltage is formed. The meshed power line structure helps to reduce the resistance on the power line, so that the voltage rise on the power line is reduced, which helps to evenly deliver the second power voltage VSS to each of the sub-pixels of the display substrate. The power line **340** is also electrically connected with the connection electrode **325** (referring to FIGS. **3B** and **6A**) in the second conductive layer **302** through a via hole **412** in the fourth insulating layer, so that the power line **340** is electrically connected with the contact hole region **400a** in the base substrate **101**, to bias the P-type substrate where the transistors **N1-N3** are located.

[0230] As shown in FIG. **8A**, the third conductive layer **303** further includes a connection electrode **333**, the connection electrode **333** is located between the first data line **241** and the second data line **242** in a data line group. As shown in conjunction with FIG. **7B**, the connection electrode **333** is electrically connected with the power line **270b** in the second conductive layer through a via hole **413** in the fourth insulating layer, for example, the number of the via **413** is at least two, so that the connection electrode **333** can fully contact with the power line **270b** to reduce the contact resistance. The parallel connection electrode **333** arranged on the power line **270b** can help to reduce the resistance on the power line **270b**, so that the voltage rise on the power line is reduced, which helps to evenly deliver the second power voltage VSS to each of the sub-pixels of the display substrate.

[0231] As shown in FIG. **3B**, FIG. **8A** and FIG. **8B**, the third conductive layer **303** further includes a connection electrode **334**, the connection electrode **334** is electrically connected with the connection electrode **323** in the second conductive layer **302** through a via hole **414** in the fourth insulating layer, so that the connection electrode **334** is connected with a second terminal **132** of the resistance device **130**. The connection electrode **334** is configured to be electrically connected with the first electrode **121** of the light-emitting element **120**. For example, the number of the via holes **414** is at least two.

[0232] As shown in conjunction with FIG. **8A** and FIG. **8B**, the third conductive layer **303** further includes a shielding electrode **341**, for example, the shielding electrode **341** is extended along the second direction D2, the shielding electrode **341** is located between a first data line **241** and a second data line **242** of a data line group, for example, the first data line **241** and the second data line **242** are symmetrically arranged on both sides of the shielding electrode **341**. The shielding electrode **341** is arranged between the two data lines to play a role of shielding and prevent signals in the two data lines from interfering with each other. For example, the shielding electrode **341** is configured to receive a constant voltage to improve the shielding ability. In this embodiment, the shielding electrode **341** is configured to receive the second power voltage VSS.

[0233] For example, the display substrate comprises a plurality of shielding electrodes **341**, the plurality of shielding electrodes **341** are arranged in a one-to-one correspondence with the plurality of data line groups, and each shielding electrode is between the first data line and the second data line of the corresponding data line group.

[0234] As shown in FIG. **8A**, the connection electrode **333**, the connection electrode **334**, and the shielding electrode **341** are arranged in the second direction D2, and are located between the first data line **241** and the second data line **242**; the connection electrode **333**, the connection electrode **334**, and the shielding electrode **341** constitute a shielding wall, which plays a role of shielding in an entire extension range of the first data line **241** and the second data line **242**, to prevent the signals in the two data lines from interfering with each other.

[0235] For example, as shown in FIG. **8A**, the connection electrode **333** and the shielding electrode **341** are located on two sides of the connection electrode **334** respectively, and are spaced apart from the connection electrode **334**. The connection electrode **333** is provided with a protruding portion **333a** at one end close to the connection electrode **334**, the protruding portion **333a** is in an L shape, a first branch of the protruding portion **333a** is extended along the first direction D1, and is connected with the main body of the connection electrode **333**, a second branch of the protruding portion **333a** is extended along the second direction D2 and the direction approaching the

connection electrode **334**, the second branch is overlapped with a gap between the connection electrode **333** and the connection electrode **334** in the first direction **D1**, so that the shielding effect is improved, and the signal crosstalk between the two data lines is further avoided.

[0236] Similarly, the shielding electrode **341** is provided with an L-shaped protruding portion **341a** at one end close to the connection electrode **334**, and the L-shaped protruding portion **341a** is used for further shielding the gap between the shielding electrode **341** and the connection electrode **334**, to improve the shielding effect.

[0237] In this way, the shielding wall achieves complete shielding in the second direction **D2**, and the first data line **241** and the second data line **242** have no area directly facing each other in the first direction **D1**, so that a better signal shielding effect is achieved, a better stability of the display data is provided, and the display effect is improved.

[0238] FIG. **9A** shows a schematic diagram of the fourth conductive layer **304**, FIG. **9B** shows the fourth conductive layer **304** on the basis of the third conductive layer **303**, and FIG. **9B** also shows via holes in the fifth insulating layer **205**, the via holes in the fifth insulating layer **205** are used to connect patterns in the third conductive layer **303** with patterns in the fourth conductive layer **304**. For clarity, only four rows and six columns of sub-pixels are shown in the figure, a dividing line of two rows of sub-pixels is shown by a dotted line; in addition, FIG. **9B** also correspondingly shows the position of the section line I-I' in FIG. **3A**.

[0239] For example, the fourth conductive layer **304** includes power lines **350** and **360** extended along the second direction **D2**. The first power line **350** is used to transmit the first power voltage **VDD**, and the power line **360** is used to transmit the second power voltage **VSS**. As shown in FIG. **9A**, the power lines **350** and the power lines **360** are alternately arranged one by one in the first direction **D1**.

[0240] For example, the plurality of power lines **350** and the plurality of power lines **330** are arranged in one-to-one correspondence, and the plurality of power lines **360** and the plurality of power lines **340** are arranged in one-to-one correspondence; in a direction perpendicular to the base substrate **101**, each power line **350** and the corresponding power line **330** overlap with each other and are electrically connected with each other (for example, in parallel), each power line **360** and the corresponding power line **340** are overlapped and are electrically connected with each other (for example, in parallel). As a result, the resistance on the power line is reduced, and the display uniformity is improved.

[0241] Referring to FIG. **9B**, the power line **350** is electrically connected with the corresponding power line **330** through a via hole **251** in the fifth insulating layer **205**, and the power line **360** is electrically connected with the corresponding power line **340** through a via hole **252** in the fifth insulating layer. For example, the numbers of the via holes **251** and **252** are at least two respectively.

[0242] With reference to FIGS. **9A** and **9B**, the fourth conductive layer **304** further includes a connection electrode **342**, the connection electrode **342** is electrically connected with the connection electrode **333** in the third conductive layer **303** through a via hole **253** in the fifth insulating layer, for example, the number of via holes **253** is at least two, so that the connection electrode **342** can fully contact the connection electrode **333** to reduce the contact resistance. Providing the connection electrode **342** helps to further reduce the resistance on the power line **270b**, so that the voltage rise on the power line is reduced, which helps to evenly deliver the second power supply voltage **VSS** to each of the sub-pixels of the display substrate.

[0243] Combining FIG. **3B**, FIG. **9A** with FIG. **9B**, the fourth conductive layer **304** further includes a connection electrode **343**, the connection electrode **343** is electrically connected with the connection electrode **334** in the third conductive layer **303** through a via hole **254** in the fifth insulating layer, so that the connection electrode **343** is connected to a second terminal **132** of the resistance device **130**. The connection electrode **343** is used for electrical connection with a first electrode **121** of the light-emitting element **120**. For example, the number of the via holes **254** is at

least two.

[0244] Combining FIG. 9A with FIG. 9B, the fourth conductive layer **304** further includes a connection electrode **344**, and the connection electrode **344** is electrically connected with the shielding electrode **341** in the third conductive layer **303** through a via hole **255** in the fifth insulating layer. As shown in FIG. 9A, the fourth conductive layer **304** further includes a connection portion **345**, which connects the connection electrode **344** to the power line **360** directly adjacent to the connection electrode **344**.

[0245] For example, as shown in FIG. 9A, the connection electrodes **344** located on two sides of the power line **360** are symmetrically arranged about the power line **360**, the power line **360**, the connection electrodes **344** on two sides of the power line **360**, and the corresponding connection portions **345** of the connection electrodes are connected with each other as an integral structure. In this way, the power line **360** can provide the second power voltage VSS to the shielding electrode **341**, to improve the shielding ability of the shielding electrode.

[0246] For example, each via hole may be additionally filled with a conductive material (such as tungsten) to conduct electricity.

[0247] FIG. 9B also shows a contact hole region **256** of the connection electrode **343**, and the contact hole region **256** is used to electrically connect with the first electrode **121** of the light-emitting element **120**.

[0248] It should be noted that along the section line I-I', a part of the connection electrode **343** in the contact hole region **256** and a part of the connection electrode **343** corresponding to the via hole **254** are not continuous (as shown in the region F in FIG. 9B); however, for the convenience of description, the contact hole region **256** and the via hole **254** are shown on the continuous connection electrode **343** in the cross-sectional schematic diagram shown in FIG. 3B, which is consistent with the actual situation. For example, as shown in FIG. 3B, the display substrate **10** further includes a sixth insulating layer **206**, and a via hole **257** is formed in the sixth insulating layer **206** corresponding to a contact hole region **256** of the connection electrode **343**, the via hole **257** is filled with a conductive material (such as tungsten), then a polishing process (such as chemical mechanical polishing) is performed to form a flat surface, which is used to form the light-emitting element **120**.

[0249] For example, the number of the via hole **257** is at least two.

[0250] For example, as shown in FIG. 3B, the numbers of the contact hole regions for electrical connection on the connection electrodes **314**, **323**, **334**, and **343** connected with the first electrode **121** of the light-emitting element **120** are at least two, respectively, the contact resistance between the connection electrodes is reduced, in turn, the connection resistance between the resistance device **130** and the first electrode **121** of the light-emitting element **120** is reduced, so that the voltage drop on a transmission path of the data signal from the resistance device **130** to the first electrode **121** is reduced, the problems such as color shift and display unevenness caused by the loss of anode potential due to the voltage drop are alleviated, and the display effect is improved.

[0251] For example, as shown in FIG. 3B, in the direction perpendicular to the base substrate **101**, the via holes **257**, **254**, and **414** corresponding to the first electrode **121** of the light-emitting element **120** do not overlap with each other. In the direction perpendicular to the substrate, stacking of the via holes leads to poor connection, disconnection or unevenness at the positions of the via holes, and this arrangement improves the electrical connection quality of the first electrode **121** of the light-emitting element **120**, and improves the display effect.

[0252] As shown in FIG. 3B, the light-emitting element **120** includes a first electrode **121**, a light-emitting layer **123**, and a second electrode **122** sequentially disposed on the sixth insulating layer **206**. For example, the first electrode **121** and the second electrode **122** are the anode and the cathode of the OLED, respectively. For example, a plurality of first electrodes **121** are arranged at intervals in a same layer, and correspond to the plurality of sub-pixels in a one-to-one correspondence. For example, the second electrode **122** is a common electrode, and is provided in

an entire surface of the display substrate **10**.

[0253] For example, as shown in FIG. **3B**, the display substrate further includes a first encapsulation layer **124**, a color filter layer **125**, and a cover plate **126** on a side of the light-emitting element **120** away from the base substrate **101**.

[0254] For example, the first encapsulation layer **124** is configured to seal the light-emitting element to prevent external moisture and oxygen from penetrating into the light-emitting element and the pixel circuit and from causing damage to the device. For example, the encapsulation layer **124** includes an organic thin film or a structure in which an organic thin film and an inorganic thin film are alternately stacked. For example, a water-absorbing layer may be arranged between the encapsulation layer **124** and the light-emitting element, and is configured to absorb residual water vapor or sol in the pre-production process of the light-emitting element. The cover plate **126** is, for example, a glass cover plate.

[0255] For example, as shown in FIG. **3B**, the display substrate may further include a second encapsulation layer **127** located between the color filter layer **125** and the cover plate **126**, and the second encapsulation layer **127** can protect the color filter layer **125**.

[0256] For example, the light-emitting element **120** is configured to emit white light, and combines the color filter layer **125** to realize a full-color display.

[0257] In other examples, the light-emitting element **120** is configured to emit light of three primary colors, in this situation, the color filter layer **125** is not necessary. The embodiment of the present disclosure does not limit the manner in which the display substrate **10** realizes full-color display.

[0258] The following Table A exemplarily shows thickness ranges and example values of the first insulating layer to the sixth insulating layer, Table B exemplarily shows thickness ranges and example values of the first conductive layer to the fourth conductive layer, Table C exemplarily shows sizes and example values of the via hole VIA2 in the second insulating layer, the via hole VIA3 in the third insulating layer, the via hole VIA4 in the fourth insulating layer, the via hole VIA5 in the fifth insulating layer, and the via hole VIA6 in the sixth insulating layer, and Table D exemplarily shows example values of the channel width, length, and respective width-to-length ratio of each transistor (N1 to N4, and P1); however, this is not a limitation to the present disclosure.

TABLE-US-00001 TABLE A Numerical Exemplary Film Layer Range (Å) Value (Å) The first insulating layer 201 30~34 32 The second insulating layer 202 10000~14000 12000 The third insulating layer 203 6500~7500 7000 The fourth insulating layer 204 6500~7500 7000 The fifth insulating layer 205 6500~7500 7000 The sixth insulating layer 206 6500~7500 7000

TABLE-US-00002 TABLE B Numerical Exemplary Film Layer Range (Å) Value (Å) The first conductive layer 201 4500~5500 5000 The second conductive layer 202 4500~5500 5000 The third conductive layer 203 4500~5500 5000 The fourth conductive layer 204 4500~5500 5000

TABLE-US-00003 TABLE C Numerical Exemplary Via Hole Range (um) Value (um) VIA2 0.2-0.3 0.22 VIA3 0.2-0.3 0.26 VIA4 0.2-0.3 0.26 VIA5 0.2-0.3 0.26 VIA6 0.3-0.4 0.36

TABLE-US-00004 TABLE D Transistor W(um)/L(um) P1 0.6/0.6 N1 0.6/0.6 N2 1.5/0.6 N3 1.02/0.76

[0259] For example, as shown in Table A, among the first insulating layer to the sixth insulating layer, a thickness of the first insulating layer **201** is the smallest, and the thickness of the second insulating layer **202** is the greatest. This is because the first insulating layer **201** includes the gate insulating layer of each transistor, and further includes the dielectric layer **104** of the storage capacitor Cst, providing the thickness of the first insulating layer **201** to be smaller can help to improve the gate control ability of the transistor to obtain a larger storage capacitor. In addition, the second insulating layer **202** serves as a field oxide layer, setting the second insulating layer **202** thicker helps an electrical isolation between the transistors. For example, the thicknesses of the third insulating layer **203**, the fourth insulating layer **204**, the fifth insulating layer **205**, and the

sixth insulating layer **206** are the same or similar; for example, the thickness of the second insulating layer **202** is 1.5 to 2 times of the thickness of the third insulating layer **203**/the fourth insulating layer **204**/the fifth insulating layer **205**/the sixth insulating layer **206**.

[0260] For example, a planar shape of each of the via holes can be a rectangular (such as square) or a circular, the size in Table C represents an average side length or an aperture of the rectangle. For example, as shown in Table C, the plurality of via holes in each of the insulating layers are provided with a same size. For example, among the second insulating layer to the sixth insulating layer, the size of the via hole in the sixth insulating layer **206** is the largest. This is because the sixth insulating layer **206** is closest to the light-emitting element, during the driving process of the light-emitting element, the current gathers up from the transistor in the bottom layer to the light-emitting element, so that the size of the via hole in the sixth insulating layer **206** is the largest, so as to transmit a larger convergent current.

[0261] For example, a distance between the first data writing transistor **P1** and the second data writing transistor **N1** ranges from 0.4 to 0.45 microns, for example, 0.42 microns, which helps to increase the pixel density. As shown in FIG. **4B**, the distance **DO** is a distance between the sides of the gate electrode **160** of the first data writing transistor **P1** and the gate electrode **170** of the second data writing transistor **N1** that are closest to each other.

[0262] For example, as shown in FIG. **4B**, an equivalent length of the resistance device **130** is 4.4 microns, and an average width of the resistance device **130** is 0.42 microns.

[0263] For example, as shown in FIG. **4B**, an effective capacitance area of the storage capacitor **Cst** is 20 square microns, that is, an effective area of the polysilicon layer **102** for forming the storage capacitor **Cst** is 20 square microns. For example, an area ratio of the storage capacitor **Cst** in each sub-pixel is 20%-35%, for example, 27%. The display substrate provided by the embodiments of the present disclosure can effectively increase the area ratio of the storage capacitor through reasonable layout, so that the capacitance value is increased.

[0264] For example, a thickness of the polysilicon layer **102** is 200 nanometers.

[0265] At least one embodiment of the present disclosure further provides a pixel structure, and the pixel structure includes a base substrate, a pixel row located on the base substrate, and a first scan line and a second scan line. The pixel row includes a plurality of sub-pixels located on the base substrate and the plurality of sub-pixels are arranged along a first direction; the first scan line and the second scan line extend along the first direction, and each of the sub-pixels includes a pixel circuit, the pixel circuit includes a data writing sub-circuit, a storage sub-circuit, and a driving sub-circuit. The data writing sub-circuit includes a first control electrode, a second control electrode, a first terminal and a second terminal, the first control electrode and the second control electrode of the data writing sub-circuit are respectively configured to receive the first control signal and the second control signal, the first terminal of the data writing sub-circuit is configured to receive a data signal, the second terminal of the data writing circuit is electrically connected with the first terminal of the storage sub-circuit, and is configured to transmit the data signal to the first terminal of the storage sub-circuit in response to the first control signal and the second control signal, the driving sub-circuit includes a control terminal, a first terminal and a second terminal, the control terminal of the driving sub-circuit is electrically connected with the first terminal of the storage sub-circuit, the first terminal of the driving sub-circuit is configured to receive the first power voltage, the second terminal of the driving sub-circuit is used to connect with the light-emitting element, the driving sub-circuit is configured to drive the light-emitting element to emit light in response to the voltage at the first terminal of the storage sub-circuit; the first scan line is electrically connected with the first control electrode of the data writing circuit of the plurality of sub-pixels to provide the first control signal; the second scan line is electrically connected with the second control electrode of the data writing circuit of the plurality of sub-pixels to provide the second control signal; the first scan line and the second scan line are provided with a same resistance, and an area of an orthographic projection of the first scan line on the base substrate is

the same as an area of an orthographic projection of the second scan line on the base substrate.

[0266] In some examples, for example, the first scan line and the second scan line refer to a portion, which is in the display region, of a wiring that transmits the corresponding control signal from the scan driving circuit to each of the sub-pixels, so that in a case of comparing the resistances and the areas, the portion of the wiring outside the display region can be ignored.

[0267] In other examples, for example, the first scan line and the second scan line may also represent all portions of the wiring that transmits the corresponding control signal from the scan driving circuit to each of the sub-pixels and include the portions of the wiring located in the display region and the non-display region, for example, the portion S shown in FIG. 1A. For example, the first control signal SEL and the second control signal SEL_B can be output by a same gate driving circuit unit (such as a GOA unit).

[0268] With this arrangement, it can be ensured that a resistance-capacitance (RC) load on the first scan line is the same as a resistance-capacitance (RC) load on the second scan line. Referring to 1A, in a case that the control signal is transmitted from the scan driving circuit 14 to each of the sub-pixels, a proportion of the portion of the scan line 11 (for example, the first scan line and the second scan line) outside the display region (shown by the dashed frame) is relatively small, so that the RC loads of the portions of the scan lines 11 in the display region are provided to be the same can improve the synchronization of the first control signal SEL and the second control signal SEL_B; with reference to FIG. 2C, for example, in a case of entering from the data writing stage 1 to the light-emitting stage 2, the above setting can make a rising edge of the first control signal SEL and a falling edge of the second control signal SEL_B occur at the same time. Therefore, the anti-interference performance of the pixel circuit is improved.

[0269] The present disclosure further provides a display substrate including a plurality of pixel structures, the plurality of pixel rows in the plurality of pixel structures are arranged in the second direction, and the first direction intersects the second direction, so that the plurality of sub-pixels of the plurality of pixel rows are a plurality of pixel columns.

[0270] It should be noted that the pixel structure provided by the embodiment of the present disclosure can be applied to the display substrate 10 provided by any one of the foregoing embodiments. However, the pixel structures provided by the embodiments of the present disclosure are not limited to a silicon-based display substrate, for example, may also be applied to a glass substrate or a flexible substrate, in this case, the light-emitting element may also be, for example, in a bottom emission structure or a double-side emission structure.

[0271] FIG. 10A shows a schematic diagram of a display substrate provided by at least one embodiment of the present disclosure. For clarity, the figure shows two rows and six columns of sub-pixels, namely only two above pixel structures. Compared with the display substrate illustrated in FIG. 3A, the display substrate omits the third conductive layer and the fourth conductive layer. In the following, the arrangement of the first scan line and the second scan line in the display substrate and the pixel structure provided by the embodiment of the present disclosure will be exemplarily described with reference to FIG. 10A, but the embodiments of the present disclosure are not limited thereto.

[0272] For example, as shown in FIG. 10A, each sub-pixel row is respectively correspondingly connected with a first scan line 210 and a second scan line 220, but the present disclosure is not limited thereto.

[0273] For example, the display substrate 10 further includes a plurality of first scan line connection portions 311 electrically connected with the first scan line 210 and a plurality of second scan line connection portions 312 electrically connected with the second scan line 220; the first scan line 210 is electrically connected with the first control electrode (that is, the gate electrode of the first data writing transistor) of the data writing circuit of a row of sub-pixels through the plurality of first scan line connection portions 311, and the second scan line 220 is electrically connected with the second control electrode (that is, the gate electrode of the second data writing

transistor) of the data writing circuit of the row of sub-pixels through the plurality of second scan line connection portions **312**.

[0274] For example, the first scan line **210** and the second scan line **220** are arranged in a same layer and insulated from each other and are made of a same material.

[0275] For example, the plurality of first scan line connection portions **311** and the plurality of second scan line connection portions **312** are arranged at intervals in a same layer and are made of a same material, and are located in a different conductive layer from the first scan line **210** and the second scan line **220**.

[0276] FIG. **10B** shows an enlarged schematic diagram of the region E in the dashed frame region in FIG. **10A**, for clarity, the figure only shows the gate electrodes of the first data writing transistor **P1** and the second data writing transistor **N1**, the first scan lines **210**, and the second scan lines **220**, and the first scan line connection portions **311** and the second scan line connection portions **312**. For the convenience of comparison, the position of the E region is also correspondingly shown in FIG. **7B**. FIG. **10C** shows a cross-sectional schematic diagram of FIG. **10B** along a section line V-V'.

[0277] For example, the lengths and the line widths of the first scan line **210** and the second scan line **220** are respectively the same.

[0278] For example, the first scan line connection portion **311** and the second scan line connection portion **312** are alternately arranged in the first direction **D1**, and the extension direction of the first scan line connection portion **311** and the extension direction of the second scan line connection portions **312** are different from the first direction **D1**. The orthographic projection of the first scan line connection portions **311** on the base substrate intersects with both the orthographic projections of the first scan line **210** and the second scan line **220** on the base substrate. The orthographic projection of the second scan line connection portions **312** on the base substrate intersect with both the orthographic projections of the first scan line **210** and the second scan line **220** on the base substrate. For example, both the first scan line connection portion **311** and the second scan line connection portion **312** are linear structures, and extend along the second direction **D2**.

[0279] For example, a sum of areas of orthographic projections of the plurality of first scan line connection portions **311** on the base substrate is the same as a sum of areas of orthographic projections of the plurality of second scan line connection portions **312** on the base substrate. Therefore, the parasitic capacitances on the plurality of first scan line connection portions **311** and the parasitic capacitances on the plurality of second scan line connection portions **312** are the same.

[0280] This setting makes the loads caused by the parasitic capacitances of the wirings (including the corresponding scan lines and connection portions) are the same while the first control signal and the second control signal respectively transmitting from the first scan line and the second scan line to the data writing sub-circuit, and the synchronization of the first control signal and the second control signal is further improved.

[0281] For example, a size of the first data writing transistor **P1** electrically connected with the first scan line and a size of the second data writing circuit **N1** electrically connected with the second scan line are the same, thus the loads generated on respective scan lines are also the same, and the synchronization of the first control signal and the second control signal is further improved, so that the anti-interference performance of the circuit is improved.

[0282] For example, each of the plurality of first scan line connection portions **311** has a same length along the second direction **D2**, and each of the plurality of first scan line connection portions **311** has a same line width. Each of the plurality of second scan line connection portions **312** has a same length in the second direction **D2**, and each of the plurality of second scan line connection portions **312** has a same line width.

[0283] For example, the first scan line **210** is electrically connected with the first scan line connection portion **311** through the via holes **231**, the second scan line **220** is electrically connected with the second scan line connection portions **312** through the via holes **232**, and the via hole **231**

and the via hole **232** are both located in the third insulating layer **203**.

[0284] For example, as shown in FIG. **10B**, the first control electrode group **191** formed by the first control electrodes of two sub-pixels adjacent in the first direction **D1** and the second control electrode group **192** formed by the second control electrodes of the two sub-pixels adjacent in the first direction **D1** are alternately arranged one by one in the first direction **D1**.

[0285] For example, as shown in FIG. **10B**, the first scan line connection portion **311** is electrically connected with the first control electrode group **191** or the first control electrode through the via hole **221**, the second scan line connection portion **312** is electrically connected with the second control electrode group **192** or the second control electrode through the via hole **222**. For example, the plurality of first scan line connection portions **311** are electrically connected with the plurality of first control electrode groups **191** in a one-to-one correspondence, and the plurality of second scan line connection portions **312** are electrically connected with the plurality of second control electrode groups **192** in a one-to-one correspondence.

[0286] For example, the first scan lines **210** and the second scan lines **220** are located on a same side of the plurality of first control electrode groups **191** and the plurality of second control electrode groups **192**, and the first scan lines **210** are closer to the plurality of first control electrode groups **191** and the second control electrode groups **192**.

[0287] For example, as shown in FIG. **10B**, in a direction perpendicular to the base substrate, the first scan lines **210** intersect with both the first scan line connection portion **311** and the second scan line connection portion **312**, and the second scan lines **220** intersect with both the first scan line connection portion **311** and the second scan line connection portion **312**. The via hole **231** is located at the intersection of the first scan line **210** and the first scan line connection portion **311**, and the via hole **232** is located at the intersection of the second scan line **220** and the second scan line connection portion **312**.

[0288] For example, as shown in FIG. **10B**, the via hole **231** and the via hole **232** are alternately arranged in the first direction **D1** and are staggered in the second direction, and the via hole **231** is closer to the plurality of the first control electrode groups **191** and the plurality of the second control electrode groups **192** than the via hole **232**.

[0289] As shown in FIG. **10B**, one end of the second scan line connection portion **312** is electrically connected with the corresponding second scan line **220** through the via hole **232**, and the other end of the second scan line connection portion **312** is electrically connected with the second control electrode or the second control electrode group to be connected through the via hole **222**. The first scan line **210** passes between the via hole **232** and the via hole **222**.

[0290] For example, as shown in FIG. **10B**, the first scan line connection portion **311** includes a main body portion **321** and an extension portion **322**, the extension portion **322** is a portion extended from the main body portion **321** and away from the first scan line **210** along the second direction. The main body portion **321** is used to electrically connect the first scan line connection portion **311** and the first control electrode or the first control electrode group, and the main body portion **321** is located between the first scan line **210** and the connected first control electrode or first control electrode group in the second direction **D2**; the extension portion **322** is located at a side of the first scan lines **210** away from the first control electrode or first control electrode group connected with the extension portion **322** in the second direction **D2**.

[0291] Here, the extension portion **322** serves as a dummy structure, and does not actually play a role of electrical connection, the extension portion **322** is arranged to make the length and the area of the first scan line connection portion **311** respectively the same as the length and the area of the second scan line connection portion **312**, thereby forming the same capacitive load on the first scan line connection portion **311** and on the second scan line connection portion **312**.

[0292] For example, as shown in FIG. **10B**, the via hole **221** is located in the middle of the first control electrode group **191**, and the via hole **222** is located in the middle of the second control electrode group **192**. The two first control electrodes in the first control electrode group **191** are

axisymmetric with respect to the first scan line connection portion **311** correspondingly connected with the first control electrode group **191** to the first control electrode group and an extension line of the first scan line connection portion **311**; and the two second control electrodes in the second control electrode group **192** are axisymmetric with respect to the second scan line connection portion **312** correspondingly connected to the second control electrode group and an extension line of the second scan line connection portion **312**.

[0293] Referring to FIG. **10A**, the first scan lines **210** correspondingly connected with two adjacent pixel rows are symmetrical about a symmetry axis along the first direction **D1**, and the second scan lines **220** corresponding to two adjacent pixel rows are symmetrical about a symmetry axis along the first direction **D1**.

[0294] The display substrate **10** includes a plurality of data lines extended along the second direction **D2**, and the data line is used to connect with the first terminal of the data writing sub-circuit in the sub-pixel to provide the data signal **Vd**.

[0295] FIG. **11A** shows a schematic diagram of a display substrate provided by other embodiments of the present disclosure, the figure shows a schematic diagram of a data line of a display substrate provided by at least one embodiment of the present disclosure, but the embodiments of the present disclosure are not limited to this case.

[0296] With reference to FIG. **8A**, the data lines are divided into a plurality of data line groups, each of the plurality of data line groups includes a first data line **241** and a second data line **242**. The plurality of data line groups are electrically connected with the plurality of pixel columns in a one-to-one correspondence to provide the data signal **Vd**. Each of the sub-pixel columns is electrically connected with a first data line **241** and a second data line **242** respectively; that is, one column of sub-pixels is driven by two data lines.

[0297] For example, as shown in FIG. **11A**, each sub-pixel column is correspondingly connected with two data lines, that is, a first data line **241** and a second data line **242**. For each column of sub-pixels, two sub-pixels in an n -th pixel row and in an $(n+1)$ -th pixel row in the plurality of pixel rows constitute a pixel group **240**, and share one data line, where n is an odd number or an even number greater than 0. For each column of sub-pixels, in the second direction **D2**, the N -th pixel group **240** is connected with the first data line **241**, and the $(N+1)$ -th pixel group **240** is connected with the second data line **242**, where N is a natural number, that is, in the second direction **D2**, the pixel group **240** is alternately connected with the first data line **241** and the second data line **242**, the odd-numbered pixel groups share one data line, and the even-numbered pixel groups share another data line.

[0298] By setting two data lines to drive a sub-pixel column, the load on each data line can be reduced, so that the driving ability of the data line is improved, the signal delay is reduced, and the display effect is improved.

[0299] Since the display substrate provided by the embodiment of the present disclosure is symmetry in structure, the layout of the signal line can be matched with the driving mode of the above-mentioned data line, to achieve the effect of optimized design.

[0300] For example, with reference to FIG. **4A**, the first electrodes of two first data writing transistors **P1** in a pixel group **240** are connected with each other as an integral structure (see region **A1**), and the first electrodes of two second data writing transistors **N1** are connected with each other as an integral structure (see region **A2**), thus in accordance with the above-mentioned driving method of the data line, a connecting via hole can be provided for the first electrodes of the integrated structure to be connected with the data line in a limited contact region, so that the data line is electrically connected with the two first data writing transistors **P1** or the two second data writing transistors **N2** in the pixel group **240**, instead of being connected with the two transistors through a via hole separately. This not only saves the process, but also makes the layout design more compact under the restriction of the design rules, and the resolution of the display substrate is improved.

[0301] FIG. 11B shows the connection structure of the data lines in two adjacent pixel groups **240**, for clarity, only partial diagrams of the sub-pixels in each of the pixel groups connected with the first data line and the second data line are selectively shown, and the partial diagrams corresponding to the two pixel groups are put together, to show the continuous relationship of signal lines, where the dotted line shows a dividing line of the two pixel groups.

[0302] As shown in FIG. 11B, in a direction perpendicular to the base substrate, the first data line **241** overlaps with the first data writing transistor **P1**, and is electrically connected with the first electrodes of two adjacent first data writing transistors **P1** in one pixel row **240**; and the second data line **242** overlaps with the second data writing transistor **N1**, and is electrically connected with the first electrodes of two adjacent second data writing transistors **N1** in one pixel group **240**.

[0303] For example, as shown in FIG. 11B, in the direction perpendicular to the base substrate, the first data line **241** overlaps with the gate electrode **160** of the first data writing transistor **P1**, the second data line **242** overlaps with the gate electrode **170** of the second data writing transistor **N1**; that is, both the first data line **241** and the second data line **242** pass through the pixel region, and no additional pixel space is occupied, to improve the space utilization.

[0304] FIG. 11C and FIG. 11D respectively show a cross-sectional schematic diagram of FIG. 11B along the section lines II-II' and III-III', and the section lines are, for example, along the first direction **D1**. For clarity, the figures only show the structure that is electrically connected with the data line, and other structures are omitted. As shown in FIGS. 11C and 11D, the first data line **241** and the second data line **242** are located in the third conductive layer **303**, and are electrically connected with the corresponding first data line connection portions **244** in the second conductive layer **302** through the via holes **403** and **404** in the fourth insulating layer **204**, respectively. In the direction perpendicular to the base substrate, the first data line connection portion **244** overlaps with the corresponding first data line **241** or the second data line **242** respectively. The first data line connection portion **244** is electrically connected with the second data line connection portion **245** in the first conductive layer **301** through the via holes **233** and **234** in the third insulating layer **203**, the second data line connection portion **245** is electrically connected with the first electrode **161** of the first data writing transistor **P1** and the first electrode **171** of the second data writing transistor **N1** through the via holes **223** and **224** in the second insulating layer **202**, respectively, so that the data signal is transmitted to the transistors.

[0305] Since the first electrodes of the two adjacent first data writing transistors **P1** and the first electrodes of the two adjacent second data writing transistors **N1** in one pixel row are respectively connected as an integral structure, and the second data line connection portion **245** electrically connects the first electrode of the first data writing transistor **P1** with the first electrode of the second data writing transistor **N1** in one sub-pixel, thus, the second data line connection portion **245** electrically connects the first electrodes **161** of the two first data writing transistors **P1** and the first electrodes **171** of the two second data writing transistors **N1** of two sub-pixels adjacent in the second direction **D2** in one sub-pixel group, and the second data line connection portion **245** is connected to the corresponding first data line **241** or the corresponding second data line **242** through the corresponding first data line connection portion **244**. It can be seen that the first electrodes of the four transistors only need to be provided with one via hole in both the third insulating layer and the fourth insulating layer to realize electrical connection with the data line, the layout space is greatly saved, and the space utilization is improved.

[0306] As shown in FIGS. 11B to 11D, for example, the first data line **241** and the second data line **242** are symmetrically arranged on two sides of the second data line connection portion **245**.

[0307] For example, as shown in FIGS. 11C and 11D, the third conductive layer further includes a shielding electrode **341**, the shielding electrode **341** is located between the first data line **241** and the second data line **242**, for example, the first data line **241** and the second data line **242** are symmetrically arranged on two sides of the shielding electrode **341**. The shielding electrode **341** is arranged between the two data lines to play a role of shielding, so as to prevent signals in the two

data lines from interfering with each other. For example, the shielding electrode **341** is configured to receive a constant voltage to improve the shielding ability; for example, the shielding electrode **341** is configured to receive the second power voltage.

[0308] For example, as shown in FIG. **4A**, the first electrodes **161** of the first data writing transistors **P1** of two sub-pixels **100** adjacent in the second direction **D2** are connected with each other as an integral structure, and the first electrodes **171** of the second data writing transistors **N1** of two sub-pixels **100** adjacent in the second direction **D2** are connected with each other as an integral structure.

[0309] For example, the materials of the above-mentioned first to fourth conductive layers are metal materials, such as gold (Au), silver (Ag), copper (Cu), aluminum (Al), molybdenum (Mo), magnesium (Mg), tungsten (W), and alloy materials of the above metals. For example, the materials of the first to fourth conductive layers may also be conductive metal oxide materials, such as indium tin oxide (ITO), indium zinc oxide (IZO), zinc oxide (ZnO), zinc aluminum oxide (AZO), and so on.

[0310] For example, the material of the first insulating layer to the sixth insulating layer is, for example, an inorganic insulating layer, such as silicon oxide, silicon nitride, silicon oxynitride, or other silicon oxide, silicon nitride or silicon oxynitride, or metal oxynitride insulating materials, for example, aluminum oxide, and titanium nitride.

[0311] For example, the light-emitting element **120** is a top emitting structure, the first electrode **121** is reflective, and the second electrode **122** is transmissive or semi-transmissive. For example, the first electrode **121** is made of a material with a high work function to act as an anode, such as an ITO/Ag/ITO laminated structure; the second electrode **122** is made of a material with a low work function to act as a cathode, for example, is a semi-transmissive metal or metal alloy material, such as an Ag/Mg alloy material.

[0312] At least one embodiment of the present disclosure further provides a display panel, which includes any one of the above display substrates **10**. It should be noted that the above-mentioned display substrate **10** provided by at least one embodiment of the present disclosure may include a light-emitting element **120**, and may also not include the light-emitting element **120**, that is, the light emitting element **120** can be formed in a panel factory after the display substrate **10** is completed. In the case that the display substrate **10** itself does not include the light-emitting element **120**, the display panel provided by the embodiment of the present disclosure further includes the light-emitting element **120** in addition to the display substrate **10**.

[0313] At least one embodiment of the present disclosure further provides a display device **40**, as shown in FIG. **12**, the display device **40** includes any one of the above-mentioned display substrates **10** or display panels, and the display device in this embodiment may be any product or component that has a display function, such as a display, an OLED panel, an OLED TV, an electronic paper, a mobile phone, a tablet computer, a notebook computer, a digital photo frame, and a navigator.

[0314] What are described above is related to only the illustrative embodiments of the present disclosure and not limitative to the protection scope of the present application. Therefore, the protection scope of the present application shall be defined by the accompanying claims.

Claims

1. A display substrate, comprising a base substrate and a first sub-pixel on the base substrate, wherein the first sub-pixel comprises a pixel circuit, and the pixel circuit comprises a data writing sub-circuit, a storage sub-circuit, and a driving sub-circuit; the data writing sub-circuit is electrically connected with a first terminal of the storage sub-circuit, and is configured to transmit a data signal to the first terminal of the storage sub-circuit in response to a control signal; the driving sub-circuit comprises a control electrode, a first electrode and a second electrode, the control

electrode of the driving sub-circuit is electrically connected with the first terminal of the storage sub-circuit, the first electrode of the driving sub-circuit is configured to receive a first power supply voltage, and the driving sub-circuit is configured to drive the light-emitting element to emit light in response to a voltage at the first terminal of the storage sub-circuit; the storage sub-circuit comprises a storage capacitor, the storage capacitor comprises a first capacitor electrode and a second capacitor electrode, and the first capacitor electrode and the second capacitor electrode respectively serve as the first terminal and a second terminal of the storage sub-circuit; the second capacitor electrode of the first sub-pixel comprises a first protrusion portion and a second protrusion portion which are both protruded along a first direction.

2. The display substrate according to claim 1, wherein the second capacitor electrode comprises a first electrode portion and a second electrode portion which are spaced apart in the first direction; and the first protrusion portion and the second protrusion portion are both a part of the second capacitor electrode.

3. The display substrate according to claim 2, wherein the second electrode portion of the second capacitor electrode comprises an electrode protrusion portion, and the electrode protrusion portion is extended along the first direction.

4. The display substrate according to claim 2, further comprising a second sub-pixel which is adjacent to the first sub-pixel in the first direction, wherein first electrode portions of second capacitor electrodes of the first sub-pixel and the second sub-pixel are in an integrated structure.

5. The display substrate according to claim 2, wherein the pixel circuit further comprises a resistance device, a first terminal of the resistance device is electrically connected with the second electrode of the driving sub-circuit, and a second terminal of the resistance device is configured to be electrically connected with the light-emitting element; and the resistance device and the control electrode of the driving sub-circuit are in a same layer and insulated from each other, and a resistivity of the resistance device is higher than a resistivity of the control electrode of the driving sub-circuit.

6. The display substrate according to claim 5, wherein the resistance device and the control electrode of the driving sub-circuit are both made of a polysilicon material.

7. The display substrate according to claim 5, wherein the first sub-pixel further comprises a connection electrode, and the connection electrode electrically connects the first terminal of the resistance device with the second electrode of the driving sub-circuit.

8. The display substrate according to claim 7, wherein the connection electrode and the second capacitor electrode are in a same layer and insulated from each other; and the first electrode portion and the second electrode portion of the second capacitor electrode are on opposite sides of the connection electrode.

9. The display substrate according to claim 1, wherein the storage capacitor further comprises a third capacitor electrode; and in a direction perpendicular to the base substrate, the third capacitor electrode is on a side of the first capacitor electrode away from the second capacitor electrode, and is configured to be electrically connected with the second capacitor electrode.

10. The display substrate according to claim 9, wherein the third capacitor electrode comprises a first electrode protrusion portion protruding along the first direction and a second electrode protrusion protruding along a second direction, and the second direction intersects with the first direction.

11. The display substrate according to claim 9, wherein the third capacitor electrode of the storage capacitor is a first region of the base substrate, and the second capacitor electrode is overlapped with the first capacitor electrode in the direction perpendicular to the base substrate.

12. The display substrate according to claim 9, wherein the third capacitor electrode comprises an electrode region and a contact region, the electrode region is overlapped with the second capacitor electrode in the direction perpendicular to the base substrate, and the second capacitor electrode is configured to be electrically connected with the electrode region through the contact region; and a

doping concentration of the contact region is higher than a doping concentration the electrode region.

13. The display substrate according to claim 1, wherein the first capacitor electrode comprises a first protrusion portion and a second protrusion portion which are both protruded in a second direction, and the second direction intersects with the first direction; and the first protrusion portion of the first capacitor electrode serves as the control electrode of the driving sub-circuit.

14. The display substrate according to claim 1, further comprising a power line extended along the first direction, wherein the power line is configured to provide the first power supply voltage to the first sub-pixel; and in a direction perpendicular to the base substrate, the power line is overlapped with the second protrusion portion of the second capacitor electrode.

15. The display substrate according to claim 1, further comprising a power line extended along the first electrode, wherein the power line is configured to provide a second power supply voltage to the first sub-pixel, and the second power supply voltage is different from the first power supply voltage; and in a direction perpendicular to the base substrate, the power line is overlapped with the first protrusion portion of the second capacitor electrode.

16. The display substrate according to claim 1, wherein the data writing sub-circuit comprises a first data writing transistor, the driving sub-circuit comprises a driving transistor, the first data writing transistor is a P-type metal-oxide semiconductor field effect transistor, and the driving transistor is an N-type metal-oxide semiconductor field effect transistor; and in a direction parallel to a plate surface of the base substrate, the first data writing transistor and the driving transistor are on opposite sides of the storage capacitor.

17. The display substrate according to claim 1, wherein the first sub-pixel further comprises a connection electrode; the connection electrode and the second capacitor electrode are in a same layer and insulated from each other, and the connection electrode electrically connects the first capacitor electrode with the data writing sub-circuit.

18. The display substrate according to claim 17, wherein the connection electrode comprises a first portion extended along the first direction and a second portion extended along a second direction, the first portion and the second portion are in an integral structure, and the first direction and the second direction are orthogonal to each other; the first portion is electrically connected with the data writing sub-circuit and the second portion is electrically connected with the first capacitor electrode.

19. The display substrate according to claim 17, wherein along a second direction, the data writing sub-circuit, the connection electrode and the driving sub-circuit are sequentially arranged, and the first direction and the second direction are orthogonal to each other.

20. A display device, comprising the display substrate of claim 1 and the light-emitting element.
