

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250278156

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

CHEN; Zesheng et al.

TOUCH FILM, TOUCHSCREEN, AND ELECTRONIC DEVICE

Abstract

A touch film, a touchscreen, and an electronic device are provided. The touch film includes a touch electrode layer and a dielectric isolation layer. The touch electrode layer includes metal lines arranged in a cross manner to form mesh units. Fractures configured to divide the metal lines into a transmit electrode and a receive electrode are provided on the metal lines, and the transmit electrode and the receive electrode form a touch capacitor structure at each of the fractures. Each of two ends of the fracture in a first direction is adjacent to two sides of at least one of the mesh units, to electrically isolate mesh units on two sides.

Inventors: CHEN; Zesheng (Dongguan, CN), ZHANG; Junyong (Dongguan, CN), WANG; Yao (Dongguan, CN), TANG; Tao (Dongguan, CN)

Applicant: HUAWEI TECHNOLOGIES CO., LTD. (Shenzhen, Guangdong, CN)

Family ID: 90789531

Appl. No.: 18/700888

Filed (or PCT Filed): October 28, 2023

PCT No.: PCT/CN2023/127431

Foreign Application Priority Data

CN 202211506848.2

Nov. 29, 2022

Publication Classification

Int. Cl.: G06F3/044 (20060101); G06F3/041 (20060101); H04M1/02 (20060101); H10K59/40 (20230101)

U.S. Cl.:

Background/Summary

[0001] This application claims priority to Chinese Patent Application No. 202211506848.2, filed with the China National Intellectual Property Administration on Nov. 29, 2022, and entitled “TOUCH FILM, TOUCHSCREEN, AND ELECTRONIC DEVICE”, which is incorporated herein by reference in its entirety.

TECHNICAL FIELD

[0002] This application relates to the field of display touchscreen technologies, and in particular, to a touch film, a touchscreen, and an electronic device.

BACKGROUND

[0003] Touch is currently a main medium for human-machine interaction. With development of touch technologies and people's requirements for higher product effect, the touch technologies develop toward a direction of lightness, thinness, and high integration.

[0004] With development of display technologies, increasingly more screen forms, such as a curved screen, a waterfall screen, a foldable screen, and a stretchable screen, appear in the public life. A mobile phone is used as an example. With continuous innovation and expansion of mobile phone forms, foldable mobile phone products have formed a high value-added product series. Folding forms include inward folding and outward folding. In an early stage of development of a foldable product, a touch solution of an add-on ultra-thin film layer is mainly used. With development of integrated touch technologies, mainstream touch solutions at present all use a current thin film packaging integrated touch solution with a relatively high integration degree.

[0005] The thin film packaging integrated touch solution is a solution in which a touch function layer is directly integrated on a flexible display panel by directly performing process steps such as thin film deposition, photoetching, and dry etching on a flexible display thin film (for example, an OLED thin film) packaging layer, and has advantages such as low costs, high integration, lightness, and thinness. Because touch electrodes are formed on one layer of metal, physical isolation between a transmit electrode (TX) and a receive electrode (RX) needs to be formed on the same layer by using fractures. However, as shown in FIG. 4, an existing fracture solution is to break at a middle position of a metal mesh formed around pixels. However, in a folding reliability test, it is found that a large stress concentration exists in the fracture at the position. Consequently, a dielectric isolation layer of a touchscreen fractures due to the stress concentration, resulting in a failure of a touch function and the screen.

SUMMARY

[0006] This application provides a touch film, a touchscreen, and an electronic device. Each fracture of a touch electrode layer is supported by at least two sides of a mesh unit. When the touch film is subject to an external pressing force or is bent, a stress value at a position of the fracture is correspondingly reduced, and a dielectric isolation layer filled in the fracture is not prone to be deformed due to a reduced stress. This improves structural strength of the touch film.

[0007] According to a first aspect, this application provides a touch film, including a touch electrode layer and a dielectric isolation layer. The touch electrode layer is located in the dielectric isolation layer. The touch electrode layer includes a plurality of metal lines, and the plurality of metal lines are arranged in a cross manner to form a plurality of polygonal mesh units. A plurality of fractures are provided on the metal lines, the plurality of fractures are configured to divide the

metal lines into a transmit electrode and a receive electrode, and the transmit electrode and the receive electrode form a touch capacitor structure at each fracture. A first direction is perpendicular to a conduction direction of each fracture, each of two ends of the fracture in the first direction is adjacent to two sides of at least one mesh unit, and the fracture is configured to electrically isolate mesh units on two sides in the conduction direction of the fracture.

[0008] In this application, the transmit electrode and the receive electrode are isolated at the touch electrode layer by using the fractures, and the transmit electrode and the receive electrode form the touch capacitor structure at each fracture, to implement a capacitive touch function of the touch film. In addition, each fracture is supported by at least two sides of the mesh unit, so that metal lines on two sides of the fracture do not form a single cantilever structure, and structural strength of the touch film at the fracture is improved. When the touch film is subject to an external pressing force or is bent, a stress value at a position of the fracture is correspondingly reduced, and the dielectric isolation layer filled in the fracture is not prone to brittle fracture due to a reduced stress. This improves the structural strength of the touch film.

[0009] In a possible implementation, the fractures include first fractures. Each first fracture is located between opposite vertex angles of at least two diagonally adjacent mesh units. The fracture is adjacent to the vertex angles, and a width of the first fracture in the first direction is within a range of 1 micrometer to 10 micrometers.

[0010] In a possible implementation, the mesh units include first mesh units. The first mesh units are located at an edge of the transmit electrode and/or the receive electrode. At least one vertex angle of each first mesh unit is adjacent to the fractures.

[0011] The first mesh units are used as edge meshes of the transmit electrode and the receive electrode. Each first mesh unit of a closed structure can enhance strength of the capacitor structure between the transmit electrode and the receive electrode. When the first mesh unit undergoes deformation such as bending, the capacitor structure is not prone to be deformed or fractured. This improves structural strength of a separation region between the transmit electrode and the receive electrode, and reduces a stress value of the dielectric isolation layer in the fractures during bending.

[0012] In a possible implementation, the mesh units include second mesh units. All side metal lines of the second mesh units are isolated from the fractures.

[0013] The second mesh units are mesh units in internal regions of the transmit electrode and the receive electrode. The second mesh units of a closed structure can improve structural strength of the transmit electrode and the receive electrode, and are not prone to be fractured when the transmit electrode and the receive electrode are deformed. This improves the structural strength of the transmit electrode and the receive electrode.

[0014] In a possible implementation, the mesh units include third mesh units. The third mesh units are communicated with the fractures, and two adjacent third mesh units are communicated with each other.

[0015] The third mesh units are of an open structure. The plurality of third mesh units are communicated with each other through the fractures, and two sides of the third mesh units are respectively the transmit electrode and the receive electrode.

[0016] In a possible implementation, the transmit electrode includes a plurality of transmit modules, and the receive electrode includes a plurality of receive modules. At least some of the transmit modules and at least some of the receive modules are disposed in a staggered manner. There is a receive module between at least some pairs of adjacent transmit modules. The touch electrode layer includes a first metal bridge, and the first metal bridge electrically connects at least two of the transmit modules. Electrical connection between adjacent transmit modules is implemented by using the first metal bridge.

[0017] In a possible implementation, the first metal bridge spans one side of the receive module and is electrically connected to the two adjacent transmit modules. The receive module between the two adjacent transmit modules is electrically isolated from the first metal bridge, to ensure the

capacitor structure between the transmit electrode and the receive electrode.

[0018] In a possible implementation, the transmit electrode includes a plurality of transmit modules, and the receive electrode includes a plurality of receive modules. At least some of the transmit modules and at least some of the receive modules are disposed in a staggered manner. There is a transmit module between at least some pairs of adjacent receive modules. The touch electrode layer includes a second metal bridge, and the second metal bridge electrically connects at least two of the receive modules. Electrical connection between adjacent receive modules is implemented by using the second metal bridge.

[0019] In a possible implementation, the second metal bridge spans one side of the transmit module and is electrically connected to the two adjacent receive modules. The transmit module between the two adjacent receive modules is electrically isolated from the second metal bridge, to ensure the capacitor structure between the transmit electrode and the receive electrode.

[0020] In a possible implementation, the transmit electrode and the receive electrode are not in a same layer in the dielectric isolation layer, to form a double-layer or multi-layer touch electrode layer structure.

[0021] In a possible implementation, the touch electrode layer includes a first connection electrode. The transmit electrode includes a plurality of transmit modules. The first connection electrode electrically connects at least two of the transmit modules. The first connection electrode and the transmit electrode are located at a same layer, to implement an electrical connection between adjacent transmit modules.

[0022] In a possible implementation, the touch electrode layer includes a second connection electrode. The receive electrode includes a plurality of receive modules. The second connection electrode electrically connects at least two of the receive modules. The second connection electrode and the receive electrode are located at a same layer, to implement an electrical connection between adjacent receive modules.

[0023] According to a second aspect, this application provides a touchscreen, including a light-emitting layer, a packaging layer, and the touch film according to any one of the foregoing descriptions. The touch film, the packaging layer, and the light-emitting layer are sequentially stacked, and a display screen having a touch function is formed by using a packaging technology and depositing the touch film on the light-emitting layer.

[0024] In a possible implementation, the light-emitting layer includes a pixel definition layer. The pixel definition layer includes a plurality of pixels. The plurality of pixels are arranged in a matrix manner, and the plurality of pixels are in a one-to-one correspondence with a plurality of mesh units in a light-emitting direction of the light-emitting layer.

[0025] In a possible implementation, a projection of each pixel on a touch electrode layer in the light-emitting direction of the light-emitting layer falls within a mesh unit corresponding to the pixel. There is a gap between a side metal line of the mesh unit and the projection that falls within the mesh unit. Each mesh unit corresponds to one pixel, and light emitted by the pixel may pass through the touch film by using the mesh unit.

[0026] In a possible implementation, a spacing between two adjacent pixels is greater than a width of a metal line, so that light emitted by each pixel in a light-emitting direction passes through a mesh unit without being blocked by the metal line.

[0027] In a possible implementation, a first plane is a plane perpendicular to the light-emitting direction of the light-emitting layer, and a spacing between the metal line and an edge of the pixel is within a range of 1 micrometer to 10 micrometers along the first plane.

[0028] In a possible implementation, the light-emitting layer includes an OLED light-emitting layer.

[0029] According to a third aspect, this application provides an electronic device, including a display screen. The display screen includes the touchscreen according to any one of the foregoing descriptions.

[0030] In a possible implementation, the electronic device includes a foldable mobile phone. The foldable mobile phone includes the display screen, and the display screen is a flexible foldable display screen.

Description

BRIEF DESCRIPTION OF DRAWINGS

- [0031] FIG. 1 is a schematic diagram of a foldable mobile phone in a folded state according to an implementation of this application;
- [0032] FIG. 2 is a schematic diagram of a foldable mobile phone in an unfolded state according to an implementation of this application;
- [0033] FIG. 3 is a schematic diagram of a structure of a touch electrode layer according to an implementation of this application;
- [0034] FIG. 4 is a schematic diagram of a structure in which fractures are provided on sides of mesh units according to this application;
- [0035] FIG. 5 is a schematic diagram of a touch electrode layer of a quadrangular mesh unit structure according to an implementation of this application;
- [0036] FIG. 6 is a structure of a touch electrode layer and a dielectric isolation layer according to an implementation of this application;
- [0037] FIG. 7 is an enlarged diagram of a part I in FIG. 5 according to this application;
- [0038] FIG. 8 is a schematic diagram of a structure of mesh units according to an implementation of this application;
- [0039] FIG. 9 is a schematic diagram of a touch electrode layer of a quadrangular mesh unit structure according to an implementation of this application;
- [0040] FIG. 10 is a schematic diagram of a touch electrode layer of a triangular mesh unit structure according to an implementation of this application;
- [0041] FIG. 11 is an enlarged diagram of a part II in FIG. 10 according to this application;
- [0042] FIG. 12 is a schematic diagram of a touch electrode layer of a triangular mesh unit structure according to an implementation of this application;
- [0043] FIG. 13 is a schematic diagram of a touch electrode layer of a triangular mesh unit structure according to an implementation of this application;
- [0044] FIG. 14 is an enlarged diagram of a part III in FIG. 13 according to this application;
- [0045] FIG. 15 is a schematic diagram of a touch electrode layer of a hexagonal mesh unit structure according to an implementation of this application;
- [0046] FIG. 16 is a schematic diagram of a connection between a first metal bridge and a transmit electrode according to an implementation of this application;
- [0047] FIG. 17 is a schematic diagram of a connection between a second metal bridge and a receive electrode according to an implementation of this application;
- [0048] FIG. 18 is a schematic diagram of a double-layer structure of a transmit electrode and a receive electrode according to an implementation of this application;
- [0049] FIG. 19 is a schematic diagram of a first connection electrode according to an implementation of this application;
- [0050] FIG. 20 is a schematic diagram of a second connection electrode according to an implementation of this application;
- [0051] FIG. 21 is a schematic sectional view of a touchscreen according to an implementation of this application;
- [0052] FIG. 22 is a relative schematic diagram of a touch electrode layer and pixels according to an implementation of this application;
- [0053] FIG. 23 is an enlarged diagram of a part IV in FIG. 21 according to this application: and

[0054] FIG. 24 is an enlarged diagram of a part V in FIG. 22 according to this application.

DESCRIPTION OF EMBODIMENTS

[0055] The following describes embodiments of this application with reference to the accompanying drawings in embodiments of this application.

[0056] For ease of understanding, the following first explains and describes English abbreviations and related technical terms used in embodiments of this application. OLED (Organic Light-Emitting Diode), also referred to as organic electroluminescence display (Organic Electroluminescence Display), is a current-type organic light-emitting device. The OLED emits light through injection and recombination of carriers. Light-emitting intensity is in direct proportion to an injected current. Under the action of an electric field, holes generated by an anode and electrons generated by a cathode of the OLED move, and are respectively injected into a hole transport layer and an electron transport layer, and migrated to a light-emitting layer. When the holes and the electrons meet in the light-emitting layer, energy excitons are generated, to excite light-emitting molecules to ultimately produce visible light.

[0057] It should be clear that the described embodiments are merely some rather than all of embodiments of this application. All other embodiments obtained by persons of ordinary skill in the art based on embodiments of this application without creative efforts shall fall within the protection scope of this application.

[0058] Terms used in embodiments of this application are merely for the purpose of describing specific embodiments, but are not intended to limit this application. The terms “a”, “the”, and “this” of singular forms used in embodiments and the appended claims of this application are also intended to include plural forms, unless otherwise specified in the context clearly.

[0059] It should be understood that the term “and/or” in this specification is merely a same field for describing associated objects and indicates that three relationships may exist. For example, A and/or B may indicate the following three cases: Only A exists, both A and B exist, and only B exists. In addition, the character “/” in this specification usually indicates an “or” relationship between associated objects.

[0060] The term “within a range” used in this specification includes two end values, for example, within a range of A to B, including end values A and B.

[0061] With development of electronic product technologies, product forms of electronic devices such as mobile phones and tablet computers become increasingly diversified. A foldable mobile phone is used as an example. An outline size of the mobile phone can be effectively reduced by mobile phone folding, so that it is convenient to carry. In early mobile phone products, due to a limitation of a touch technology, input of a mobile phone is generally implemented by a keyboard. The keyboard and a display screen are two components connected by using a transmission data link. It is easy to implement folding of the mobile phone. Currently, a display screen of a mobile phone generally has a touch function, so that input and display output of the mobile phone are integrated, and a size of a display screen of the mobile phone may be increased to 6.74 inches. There are various technical means for implementing light, thin, and highly integrated touch technologies, for example, a full lamination technology, including add-on solutions such as GFF, OGS, GF2, Metalmesh, and OGM, and solutions such as TOE (Touch on Encapsulation). On-cell, and In-cell that are directly integrated with a display panel.

[0062] As people have an increasing requirement for functions of a mobile phone, a size of a mobile phone screen also needs to be continuously increased to meet a display requirement of people for the mobile phone. The increase in the size of the mobile phone screen affects portability of the mobile phone. A setting-out size of the mobile phone can be effectively reduced by mobile phone folding. In addition, development of an existing flexible touchscreen implements screen folding, so that a whole screen can be folded into two split screens, and content of different sizes is displayed in different mobile phone forms.

[0063] With emergence of a foldable mobile phone, a size of a display screen when the mobile

phone is used is effectively increased. Refer to FIG. 1 and FIG. 2. FIG. 1 is a state diagram of a foldable mobile phone **500** when the foldable mobile phone **500** is folded. A screen of the mobile phone in a folded state may be in an outward folding form (the screen in the folded state is located on an outer side surface of the mobile phone, as shown in FIG. 1, both an upper side and a lower side are display screens, and in this case, the screen of the mobile phone can still display information). Alternatively, a screen of the mobile phone in a folded state may be in an inward folding form (the screen in the folded state is located on a folded inner side of the mobile phone, as shown in FIG. 1, both an upper side surface and a lower side surface are housings, the screen is folded and hidden inside the mobile phone, and the screen can be displayed only when the mobile phone is unfolded). FIG. 2 is a state diagram of the foldable mobile phone **500** when the foldable mobile phone **500** is unfolded. In FIG. 1, a lower half part of the mobile phone in the folded state is rotated by 180 degrees in a counterclockwise manner, to present the mobile phone in an unfolded state shown in FIG. 2. In this implementation, a mobile phone in an outward folding form is used as an example, and an entire plane on an upper side in FIG. 2 is a screen.

[0064] The foldable mobile phone **500** is switched reciprocally between the folded state and the unfolded state in use, and therefore has a high requirement for structural strength of a flexible screen. For an existing flexible screen, for example, an OLED display screen, an inorganic isolation layer is generally deposited on flexible OLEDs, and then physical electrodes required for a touchscreen are formed in a connection manner such as metal deposition, patterning, and bridge electrical connection.

[0065] FIG. 3 is a schematic diagram of a structure of a touch electrode layer. Electrodes include a first electrode **170**) and a second electrode **180**. As shown in FIG. 3, shaded electrode blocks (the shadow is merely used for distinguishing from the second electrode when being displayed in FIG. 3, and in practice, a style of the first electrode **170** may be the same as that of the second electrode **180**, or a color of the first electrode **170** may be different from that of the second electrode **180**) in FIG. 3 are connected in series to form the first electrode **170**, and blank electrode blocks in FIG. 3 are connected in series to form the second electrode **180**. The first electrode **170**) extends in a horizontal direction shown in FIG. 3, and the second electrode **180**) extends in a longitudinal direction shown in FIG. 3. The first electrode **170** and the second electrode **180** are stacked in an up-down manner at a staggered position. In addition, the first electrode **170**) and the second electrode **180** are electrically isolated from each other at the staggered position. In this application, electrical isolation means that an electrical connection is isolated, to be specific, an electrical connection between the first electrode **170**) and the second electrode **180** is isolated at the staggered position. For example, a bridge structure may be disposed at the staggered position between the first electrode **170** and the second electrode **180** to implement electrical isolation between the first electrode **170** and the second electrode **180**. Two adjacent electrode plates in the first electrode **170** are connected through a bridge, the bridge passes through a bottom side of the second electrode **180**, and a specific gap is reserved between the bridge and the second electrode **180**; and/or two adjacent electrode plates in the second electrode **180** are connected through a bridge, the bridge passes through an upper side of the first electrode **170**, and a specific gap is reserved between the bridge and the first electrode **170**.

[0066] For the foregoing flexible display screen, a touch film with electrodes may be integrated on the flexible OLED, and presents a mesh structure shown in FIG. 4. FIG. 4 is a schematic diagram of a structure in which fractures are provided on sides of mesh units. There are hollow parts in the middle of a metal mesh (metal mesh). The hollow parts are opposite to pixels of the OLED, and each hollow part is opposite to one pixel, to form a flexible OLED touchscreen having a touch function.

[0067] As shown in FIG. 4, an existing thin film touch metal mesh (metal mesh) is formed after patterning of primary metal film formation, and therefore is located at a same laminated spatial position in a light-emitting direction of the OLED (a direction perpendicular to a plane in which

FIG. 4 is located). To form a transmit electrode (TX) and a receive electrode (RX) on the metal mesh and implement a physical function of capacitive touch, the transmit electrode (TX) and the receive electrode (RX) need to be physically disconnected. Currently, fractures **111** with a width less than 10 μm are generally provided, to form physical electrical isolation at two ends of each fracture. As shown in FIG. 4, the fractures **111** are usually located at middle positions of meshes of the mesh units. The metal meshes on two sides of the fractures are respectively a transmit electrode **130** and a receive electrode **140**. The transmit electrode **130** and the receive electrode **140** form a capacitor structure at each fracture. In FIG. 4, a dashed line sequentially passes through each fracture **111**, and two sides of the dashed line are separated by the fractures **111** into the transmit electrode **130** and the receive electrode **140**. When a finger is in contact with an outer side surface of the touchscreen formed by the touch film, a capacitor voltage at a contact position changes, and a touch position is determined based on the capacitance change. However, in the foregoing disconnection manner, a section of metal is bound to be in a suspended state. When the touchscreen of a bent part of the foldable mobile phone is bent, a stress concentration is formed at positions of the fractures **111**. Consequently, a dielectric isolation layer of the touchscreen fractures due to the stress concentration, resulting in a failure of the touch function and the screen. In addition, for a non-foldable mobile phone, when a screen of the mobile phone is subject to a large stress, a brittle fracture may also occur on a dielectric isolation layer at fractures due to a stress concentration, resulting in a failure of a touch function and the screen.

[0068] To improve structural strength of a touchscreen. this application provides a touch film. Refer to FIG. 5 and FIG. 6. FIG. 5 is a schematic diagram of a touch electrode layer **100** of a quadrangular mesh unit structure in the touch film. FIG. 6 is a schematic diagram of a part of the touch electrode layer **100** and a dielectric isolation layer **200** in the touch film. In FIG. 6, a part of the dielectric isolation layer **200** above the touch electrode layer **100** is hidden, to better display a relative position relationship between the touch electrode layer **100** and the dielectric isolation layer **200**.

[0069] The touch film includes the touch electrode layer **100** and the dielectric isolation layer **200**. The touch electrode layer **100** is located in the dielectric isolation layer **200**. The touch electrode layer **100** includes a plurality of metal lines **110**. A part of the metal lines **110** are first metal lines, and the first metal lines are parallel to each other and extend in a lower left direction. The other part of the metal lines **110** are second metal lines, and the second metal lines are parallel to each other and extend in a lower right direction. The two parts of the metal lines **110** are arranged in a cross manner to form the mesh-shaped touch electrode layer **100**. The touch electrode layer **100** may also be referred to as a metal mesh (metal mesh).

[0070] A polygonal unit enclosed by a plurality of adjacent metal lines is a mesh unit **120**. The touch electrode layer **100** includes a plurality of mesh units **120**. The mesh units **120** are polygonal. Some mesh units **120** have a same size, and some mesh units **120** have different sizes. Specifically, the mesh unit **120** includes a plurality of side metal lines and a cavity region enclosed by the metal lines. In this implementation, a quadrangular mesh unit **120** is used as an example.

[0071] FIG. 7 is an enlarged diagram of a part I in FIG. 5, to display the fractures **111** more clearly. The fractures **111** are provided on the metal lines **110**. Specifically, a first direction is a direction perpendicular to a conduction direction of each fracture **111**, each of two ends of the fracture **111** in the first direction is adjacent to two sides of at least one mesh unit, and the fracture **111** is configured to electrically isolate (not conduct) mesh units **120** on two sides in the conduction direction of the fracture **111**. Each of the two ends of the fracture **111** in the first direction is adjacent to the two sides of the at least one mesh unit, so that metal lines on the two sides of the fracture **111** do not form a single cantilever structure, but are jointly supported by the at least two metal lines of the mesh unit, so that structural strength of the touch film at the fracture is improved. When the touch film is subject to an external pressing force or is bent, a stress value at a position of the fracture is correspondingly reduced, and the dielectric isolation layer filled in the fracture is not

prone to brittle fracture due to a reduced stress. This improves the structural strength of the touch film.

[0072] Specifically, as shown in FIG. 7, the fractures **111** in this implementation include first fractures **112**. Each first fracture **112** is located between two opposite vertex angles **121** of two diagonally adjacent mesh units **120**.

[0073] In this application, “diagonally adjacent” means that two mesh units **120** are adjacent in a diagonal direction. As shown in FIG. 7, a mesh unit A is used as an example. The mesh unit A is provided with four mesh units C that are adjacent to the mesh unit A on sides, and the mesh unit A and each mesh unit C that are adjacent to each other on the side share a same side. The mesh unit A is provided with four mesh units B that are diagonally adjacent to the mesh unit A, and the mesh unit A and each mesh unit B that is diagonally adjacent to the mesh unit A have opposite angles.

[0074] As shown in FIG. 7, the mesh unit A is used as an example. There is a first fracture **112** between the mesh unit A and the mesh unit B on a right side of the mesh unit A, and a touch capacitor structure is formed between the mesh unit A and the mesh unit B on the right side of the mesh unit A. As shown in FIG. 5, a plurality of first fractures **112** are provided on the touch electrode layer **100**, and the plurality of first fractures **112** are arranged according to a specific rule, to divide the metal lines **110** into the transmit electrode **130** and the receive electrode **140**. The transmit electrode **130** and the receive electrode **140** are electrically isolated at each first fracture **112**, so that the transmit electrode **130** and the receive electrode **140** form a touch capacitor structure at the first fracture **112**.

[0075] In this implementation, the first fractures **112** on the touch electrode layer **100** are provided at vertex angles of the mesh units **120**. The transmit electrode **130** and the receive electrode **140** are isolated by using the first fractures **112**, and the transmit electrode **130** and the receive electrode **140** form the touch capacitor structure at each first fracture **112**, to implement a capacitive touch function of the touch film. In addition, the first fractures **112** located at the vertex angles of the mesh units **120** eliminate physical existence space of suspended metal. When the touch film is subject to the external pressing force or is bent, a stress value at a position of the first fracture **112** is correspondingly reduced, and the dielectric isolation layer filled in the first fracture **112** is not prone to brittle fracture due to a reduced stress. This improves the structural strength of the touch film.

[0076] Specifically, a reciprocal bending test is performed on the touch electrode layer **100** (the fractures are located at the sides of the mesh units) shown in FIG. 4 and the touch electrode layer **100** (the fractures are located at the vertex angles of the mesh units) shown in FIG. 5. In a bending process, a stress on the fractures in a bending region is tested, and a strain concentration factor of the fractures at the sides of the mesh units is 1.676, and a strain concentration factor of the fractures at the vertex angles of the mesh units is 1.503. In comparison with the fractures located at the sides of the mesh units, the strain concentration factor of the fractures located at the vertex angles of the mesh units may be reduced by 10.32%. This effectively reduces a stress degree of the touchscreen under deformation such as bending, and avoids damages such as fracture of the touch film after the touch film is bent for a plurality of times.

[0077] In a possible implementation, as shown in FIG. 7, a width of the first fracture **112** is within a range of 1 micrometer to 10 micrometers. The width of the first fracture **112** is a width of the first fracture **112** in the first direction, and the first direction is a direction of a connection line between two diagonally adjacent mesh units **120** that are separated by the first fracture **112**. For example, in FIG. 7, a direction indicated by an arrow corresponding to a position of each first fracture **112** is the first direction corresponding to the first fracture **112**. The first direction may alternatively be a reverse direction of the direction indicated by the arrow shown in FIG. 7.

[0078] The mesh unit A is used as an example. A fracture is provided between the mesh unit A and the mesh unit B on the right side. A direction of a connection line between the mesh unit A and the mesh unit B is the first direction. The width of the first fracture **112** in the first direction is within

the range of 1 micrometer to 10 micrometers, to ensure that the transmit electrode **130** and the receive electrode **140** form effective electrical isolation at each fracture **111**, and form the touch capacitor structure.

[0079] In a possible implementation, as shown in FIG. 5 and FIG. 8, the mesh units **120** include first mesh units **122**. The first mesh unit **122** is located at an edge of the transmit electrode **130** and the receive electrode **140**, and at least one vertex angle of each first mesh unit **122** is adjacent to the fractures **111**. Each first mesh unit **122** is provided with at least one next-nearest neighbor mesh unit. For example, the mesh unit A in FIG. 7 is one of the first mesh units **122**, the first mesh unit **122** is provided with four next-nearest neighbor mesh units B. Each next-nearest neighbor mesh unit in this implementation is diagonally adjacent to the first mesh unit **122**. In addition, there is a first fracture **112** between the first mesh unit **122** and an opposite vertex angle **121** of at least some of the next-nearest neighbor mesh units, and the first fracture **112** electrically isolates the first mesh unit **122** from the next-nearest neighbor mesh unit.

[0080] In this implementation, there is no fracture **111** on the metal lines **110** enclosing the first mesh unit **122**. The first mesh unit **122** is not communicated with a mesh unit that is adjacent to the first mesh unit **122** on a side, and the first mesh unit **122** is not communicated with a mesh unit that is diagonally adjacent to the first mesh unit **122** either. The first mesh unit **122** is enclosed by the metal lines **110** to form a closed structure. For the first mesh units **122** located in the bending region of the touchscreen, the first mesh units **122** are used as edge meshes of the transmit electrode **130** and the receive electrode **140**. Each first mesh unit **122** of a closed structure can enhance strength of the capacitor structure between the transmit electrode **130** and the receive electrode **140**. When the first mesh unit **122** undergoes deformation such as bending, the capacitor structure is not prone to be deformed or fractured. This improves structural strength of a separation region between the transmit electrode **130** and the receive electrode **140**, and reduces a stress value of the dielectric isolation layer in the fractures **111** during bending. In this application, the main purpose is to reduce a stress value of an inorganic layer in the dielectric isolation layer during bending.

[0081] The transmit electrode **130** includes a plurality of mesh units **120**, and the receive electrode **140** also includes a plurality of mesh units **120**. As shown in FIG. 6 and FIG. 8, an example in which an upper part is the transmit electrode **130** and a lower part is the receive electrode **140** is used. The fractures **111** are arranged in a sawtooth-like route between the transmit electrode **130** and the receive electrode **140**, to form the transmit electrode **130** and the receive electrode **140** that are located in a cross staggered manner. The edge meshes of the transmit electrode **130** and the receive electrode **140** are the first mesh units **122**. Each fracture **111** is provided between the first mesh unit **122** of the transmit electrode **130** and the first mesh unit **122** of the receive electrode **140**, to form the touch capacitor structure.

[0082] In this implementation, for some mesh units, there is a fracture **111** between each of the mesh units and at least one next-nearest neighbor mesh unit of the mesh unit. The mesh units are the first mesh units **122**. The first mesh units **122** are mesh units at edges of the transmit electrode **130** and the receive electrode **140**. Two sides that are of the first mesh unit **122** and that are adjacent to the fracture **111** play a main support role for the metal lines at the fracture **111**.

[0083] In a possible implementation, as shown in FIG. 8, the mesh units **120** include second mesh units **123**. All side metal lines of the second mesh units **123** are isolated from the fractures **111**. All side metal lines of the second mesh units **123** are not directly connected to the fractures **111**, but are separated by a spacing of a side width of at least one mesh unit **120**. Each second mesh unit **123** is provided with at least one next-nearest neighbor mesh unit, and each next-nearest neighbor mesh unit is diagonally adjacent to the second mesh unit **123** that matches the next-nearest neighbor mesh unit. The second mesh unit **123** is electrically connected to all the next-nearest neighbor mesh units corresponding to the second mesh unit **123** at opposite vertex angles, and no fracture **111** is provided between the second mesh unit **123** and all the next-nearest neighbor mesh units

corresponding to the second mesh unit **123**. For example, in FIG. 7, a mesh unit C at the upper left or lower left of the mesh unit A is one of the second mesh units **123**, and no fracture **111** is provided between the second mesh unit **123** and a mesh unit that is diagonally adjacent to the second mesh unit **123**. The second mesh unit **123** is not located in the adjacent edge meshes the transmit electrode **130** and the receive electrode **140**, but is located in internal meshes of the transmit electrode **130** and the receive electrode **140**.

[0084] In this implementation, there is no fracture **111** on the metal lines **110** enclosing the second mesh unit **123**. The second mesh unit **123** is not communicated with a mesh unit that is adjacent to the second mesh unit **123** on a side, and the second mesh unit **123** is not communicated with a mesh unit that is diagonally adjacent to the second mesh unit **123** either. The second mesh unit **123** is enclosed by the metal lines **110** to form a closed structure. The second mesh units **123** are mesh units in internal regions of the transmit electrode **130** and the receive electrode **140**. Each second mesh unit **123** of the closed structure can improve structural strength of the transmit electrode **130** and the receive electrode **140**, and is not prone to be fractured when the transmit electrode **130** and the receive electrode **140** are deformed. This improves the structural strength of the transmit electrode **130** and the receive electrode **140**.

[0085] In a possible implementation, as shown in FIG. 8, the mesh units **120** include third mesh units **124**. Each third mesh unit **124** is communicated with the fractures **111**, and two adjacent third mesh units **124** are communicated with each other. Each third mesh unit **124** is provided with a plurality of next-nearest neighbor mesh units, and the third mesh unit **124** is diagonally adjacent to the next-nearest neighbor mesh units corresponding to the third mesh unit **124**. A fracture **111** is provided between at least some of the next-nearest neighbor mesh units corresponding to the third mesh unit **124** and the third mesh unit **124**. A second direction is a direction of a connection line between the third mesh unit **124** and each next-nearest neighbor mesh unit corresponding to the third mesh unit **124**. For example, a direction of a connection line between two adjacent third mesh units **124** in FIG. 8 is the second direction, and the conduction direction of the fracture **111** is consistent with the second direction.

[0086] In this implementation, the third mesh units **124** are of an open structure, and the metal lines **110** around the third mesh units **124** are disconnected at the vertex angles to form fracture **111** structures. In addition, a plurality of third mesh units **124** are communicated with each other through the fractures **111**. Two sides of the third mesh units **124** are respectively the transmit electrode **130** and the receive electrode **140**. The touch electrode layer **100** forms the touch capacitor structures at the plurality of communicated third mesh units **124**.

[0087] In a possible implementation, as shown in FIG. 9, the fractures **111** provided on the touch film may alternatively include second fractures **113**. Both ends of each second fracture **113** are separately adjacent to at least two side metal lines of the first mesh unit **122**. In this implementation, as shown in FIG. 9, after the entire metal mesh is deposited, the metal lines at positions indicated by double dashed lines in FIG. 9 are etched off, to form the second fractures **113** in this implementation. A conduction direction of the second fracture **113** is communicated with the third mesh units **124** on two sides, to form a separation capacitor structure between the transmit electrode **130** and the receive electrode **140**.

[0088] Two sides of each third mesh unit **124** are removed to form the second fracture **113**, and the second fracture **113** is communicated with the third mesh unit **124** to form a capacitor channel structure. One vertex angle of the first mesh unit **122** located at the edges of the transmit electrode **130** and the receive electrode **140** is adjacent to the second fracture **113**, and at least two sides of the first mesh unit **122** provide support for the second fracture **113**.

[0089] Specifically, all side metal lines of the second mesh units **123** are isolated from the second fractures **113**. All side metal lines of the second mesh units **123** are not directly connected to the second fractures **113**, but are separated by a spacing of a side width of at least one mesh unit **120**. There is no second fracture **113** on the metal lines **110** enclosing the second mesh unit **123**. The

second mesh unit **123** is not communicated with a mesh unit that is adjacent to the second mesh unit **123** on a side, and the second mesh unit **123** is not communicated with a mesh unit that is diagonally adjacent to the second mesh unit **123** either. The second mesh unit **123** is enclosed by the metal lines **110** to form a closed structure. The second mesh units **123** are mesh units in internal regions of the transmit electrode **130** and the receive electrode **140**. Each second mesh unit **123** of the closed structure can improve structural strength of the transmit electrode **130** and the receive electrode **140**, and is not prone to be fractured when the transmit electrode **130** and the receive electrode **140** are deformed. This improves the structural strength of the transmit electrode **130** and the receive electrode **140**.

[0090] In a possible implementation, as shown in FIG. **10**, the mesh units **120** shown in this implementation are triangular.

[0091] As shown in FIG. **11**, the fractures **111** provided on the touch film in this implementation are first fractures **112**. As shown in FIG. **11**, a mesh unit A is used as an example. The mesh unit A is provided with three mesh units B that are adjacent to the mesh unit A on sides, and is further provided with nine mesh units C that are diagonally adjacent to the mesh unit A. The mesh unit A is disconnected from two mesh units C below to form one first fracture **112**, and each mesh unit B is disconnected from two mesh units C on a right side to form one first fracture **112**. The first fracture **112** is located between two diagonally adjacent mesh units **120**. In addition, the first fracture **112** described in this implementation may be located between a plurality of pairs of two diagonally adjacent mesh units **120**.

[0092] A direction indicated by a direction of a straight line arrow shown in FIG. **11** may be a first direction, and the first direction is perpendicular to a conduction direction of the fracture **111**. Both ends of each first fracture **112** in the first direction are adjacent to two sides of two mesh units, the two mesh units share one side, and the three metal lines jointly support the corresponding first fracture **112**. In addition, a width of the first fracture **112** in the first direction may be within a range of 1 micrometer to 10 micrometers.

[0093] As shown in FIG. **10** and FIG. **11**, there are a plurality of first fractures **112**, and the plurality of first fractures **112** are communicated. In addition, a third mesh unit **124** is communicated between two adjacent first fractures **112**, and the transmit electrode **130** and the receive electrode **140** form a capacitor structure at the first fracture **112**.

[0094] First mesh units **122** are located at an edge of the transmit electrode **130** and the receive electrode **140**. At least one vertex angle of each first mesh unit **122** is adjacent to the first fractures **112**. Two sides of the first mesh unit **122** that are close to the fracture **111** play a main support role for the metal line at the fracture **111**.

[0095] All side metal lines of the second mesh units **123** are isolated from the first fractures **112**. All side metal lines of the second mesh units **123** are not directly connected to the first fractures **112**, but are separated by a spacing of a side width of at least one mesh unit **120**. There is no first fracture **112** on the metal lines **110** enclosing the second mesh unit **123**. The second mesh unit **123** is not communicated with a mesh unit that is adjacent to the second mesh unit **123** on a side, and the second mesh unit **123** is not communicated with a mesh unit that is diagonally adjacent to the second mesh unit **123** either. The second mesh unit **123** is enclosed by the metal lines **110** to form a closed structure. The second mesh units **123** are mesh units in internal regions of the transmit electrode **130** and the receive electrode **140**. Each second mesh unit **123** of the closed structure can improve structural strength of the transmit electrode **130** and the receive electrode **140**, and is not prone to be fractured when the transmit electrode **130** and the receive electrode **140** are deformed. This improves the structural strength of the transmit electrode **130** and the receive electrode **140**.

[0096] In a possible implementation, as shown in FIG. **12**, the mesh units **120** shown in this implementation are triangular. The fractures **111** provided on the touch film may alternatively include second fractures **113**. Both ends of each second fracture **113** are separately adjacent to at least two side metal lines of the first mesh unit **122**. In this implementation, as shown in FIG. **12**,

after the entire metal mesh is deposited, the metal lines at positions indicated by double dashed lines in FIG. 12 are etched off, to form the second fractures 113 in this implementation. A conduction direction of the second fracture 113 is communicated with the third mesh units 124 on two sides, to form a separation capacitor structure between the transmit electrode 130 and the receive electrode 140.

[0097] Two sides of each third mesh unit 124 are removed to form the second fracture 113, and the second fracture 113 is communicated with the third mesh unit 124 to form a capacitor channel structure. One vertex angle of the first mesh unit 122 located at the edges of the transmit electrode 130 and the receive electrode 140 is adjacent to the second fracture 113, and at least two sides of the first mesh unit 122 provide support for the second fracture 113.

[0098] Specifically, all side metal lines of the second mesh units 123 are isolated from the second fractures 113. All side metal lines of the second mesh units 123 are not directly connected to the second fractures 113, but are separated by a spacing of a side width of at least one mesh unit 120. There is no second fracture 113 on the metal lines 110 enclosing the second mesh unit 123. The second mesh unit 123 is not communicated with a mesh unit that is adjacent to the second mesh unit 123 on a side, and the second mesh unit 123 is not communicated with a mesh unit that is diagonally adjacent to the second mesh unit 123 either. The second mesh unit 123 is enclosed by the metal lines 110 to form a closed structure. The second mesh units 123 are mesh units in internal regions of the transmit electrode 130 and the receive electrode 140. Each second mesh unit 123 of the closed structure can improve structural strength of the transmit electrode 130 and the receive electrode 140, and is not prone to be fractured when the transmit electrode 130 and the receive electrode 140 are deformed. This improves the structural strength of the transmit electrode 130 and the receive electrode 140.

[0099] In a possible implementation, as shown in FIG. 13 and FIG. 14, the mesh units 120 shown in this implementation are triangular. The fractures 111 provided on the touch film may alternatively include first fractures 112 and second fractures 113.

[0100] A direction indicated by a direction of a straight line arrow shown in FIG. 14 may be a first direction, and the first direction is perpendicular to a conduction direction of the fracture. Both ends of each first fracture 112 in the first direction are adjacent to two sides of two mesh units, the two mesh units share one side, and the three metal lines jointly support the corresponding first fracture 112.

[0101] Both ends of each second fracture 113 are separately adjacent to at least two side metal lines of a first mesh unit 122. In this implementation, as shown in FIG. 14, after the entire metal mesh is deposited, the metal lines at positions indicated by double dashed lines in FIG. 14 are etched off, to form the second fractures 113 in this implementation. A conduction direction of the second fracture 113 is communicated with the third mesh units 124 on two sides, to form a separation capacitor structure between the transmit electrode 130 and the receive electrode 140.

[0102] In a possible implementation, as shown in FIG. 15, the mesh units 120 shown in this implementation are hexagonal. The fractures 111 provided on the touch film may include second fractures 113.

[0103] Both ends of each second fracture 113 are separately adjacent to at least two side metal lines of a first mesh unit 122. In this implementation, as shown in FIG. 15, after the entire metal mesh is deposited, the metal lines at positions indicated by double dashed lines in FIG. 15 are etched off, to form the second fractures 113 in this implementation. A conduction direction of the second fracture 113 is communicated with the third mesh units 124 on two sides, to form a separation capacitor structure between the transmit electrode 130 and the receive electrode 140.

[0104] In a possible implementation, as shown in FIG. 5, the transmit electrode 130 includes a plurality of transmit modules 131, and the receive electrode 140 includes a plurality of receive modules 141. At least some of the transmit modules 131 and at least some of the receive modules 141 are disposed in a staggered manner. There is a receive module 141 between at least some pairs

of adjacent transmit modules **131**.

[0105] FIG. **16** is a schematic diagram of a connection between a first metal bridge and a transmit electrode. An upper part is a touch film layer. The touch film layer includes a touch electrode layer **100** and a dielectric isolation layer **200**. The touch electrode layer **100** includes a transmit electrode **130** and a receive electrode **140**. The transmit electrode **130** and the receive electrode **140** are electrically isolated from each other, to form a touch capacitor structure.

[0106] As shown in FIG. **16**, two adjacent transmit modules **131** are separated by one receive module **141**. The touch electrode layer **100** includes a first metal bridge **150**, and the first metal bridge **150** is electrically connected to at least two transmit modules **131**. In this implementation, that the first metal bridge **150** electrically connects two transmit modules **131** is used as an example. The first metal bridge **150** may also electrically connect three or more transmit modules **131** by extending a length of the first metal bridge **150**. It should be noted that, for an entire screen, the touch electrode layer **100** of a touch film of the screen is divided into a plurality of transmit modules **131** and a plurality of receive module **141**. The plurality of transmit modules **131** are electrically connected to form a whole, and the plurality of receive modules **141** are electrically connected to form a whole.

[0107] Specifically, some receive modules **141** are each located between two adjacent transmit modules **131**. The first metal bridge **150** spans one side of the receive module **141** and is electrically connected to the two adjacent transmit modules **131**. The first metal bridge **150** may span a bottom side of the receive module **141** in the middle.

[0108] The two adjacent transmit modules **131** are electrically connected through the first metal bridge **150**. The receive module **141** located between the two adjacent transmit modules **131** is electrically isolated from the first metal bridge **150**. The first metal bridge **150** is not in contact with the receive module **141**. Specifically, the dielectric isolation layer **200** may be filled between the first metal bridge **150** and the receive module **141**.

[0109] In a possible implementation, as shown in FIG. **5**, the transmit electrode **130** includes a plurality of transmit modules **131**, and the receive electrode **140** includes a plurality of receive modules **141**. At least some of the transmit modules **131** and at least some of the receive modules **141** are disposed in a staggered manner. There is a receive module **141** between at least some pairs of adjacent transmit modules **131**.

[0110] FIG. **17** is a schematic diagram of a connection between a second metal bridge and a receive electrode. An upper part is a touch film layer. The touch film layer includes a touch electrode layer **100** and a dielectric isolation layer **200**. The touch electrode layer **100** includes a transmit electrode **130** and a receive electrode **140**. The transmit electrode **130** and the receive electrode **140** are electrically isolated from each other, to form a touch capacitor structure.

[0111] As shown in FIG. **17**, two adjacent receive modules **141** are separated by one transmit module **131**. The touch electrode layer **100** includes a second metal bridge **160**, and the second metal bridge **160** electrically connects at least two receive modules **141**. In this implementation, that the second metal bridge **160** electrically connects two receive modules **141** is used as an example. The second metal bridge **160** may also electrically connect three or more receive electrodes **140** by extending a length of the second metal bridge **160**.

[0112] Specifically, some transmit modules **131** are each located between two adjacent receive modules **141**. The second metal bridge **160** spans one side of the transmit module **131** and is electrically connected to the two adjacent receive modules **141**. The second metal bridge **160** may span a bottom side of the transmit module **131** in the middle.

[0113] The two adjacent receive modules **141** are electrically connected through the second metal bridge **160**. The transmit module **131** located between the two adjacent receive modules **141** is electrically isolated from the second metal bridge **160**. The second metal bridge **160** is not in contact with the transmit module **131**. Specifically, the dielectric isolation layer **200** may be filled between the second metal bridge **160** and the transmit module **131**.

[0114] In a possible implementation, as shown in FIG. 5, the transmit electrode **130** includes a plurality of transmit modules **131**, and the receive electrode **140** includes a plurality of receive modules **141**. At least some of the transmit modules **131** and at least some of the receive modules **141** are disposed in a staggered manner. There is a receive module **141** between at least some pairs of adjacent transmit modules **131**.

[0115] As shown in FIG. 18, in this implementation, the transmit electrode **130** and the receive electrode **140** are not in a same layer in the dielectric isolation layer **200**. The transmit electrode **130** and the receive electrode **140** are of a double-layer structure. The fractures **111** are located between layers at which the transmit electrode **130** and the receive electrode **140** are located.

[0116] Specifically, as shown in FIG. 19, the touch electrode layer **100** includes a first connection electrode **132**. The first connection electrode **132** electrically connects at least two transmit modules **131**. In this implementation, an example in which the first connection electrode **132** electrically connects two transmit modules **131** is used. The first connection electrode **132** and the transmit electrode **130** are located at a same layer.

[0117] Specifically, as shown in FIG. 20, the touch electrode layer **100** includes a second connection electrode **142**. The second connection electrode **142** electrically connects at least two receive modules **141**. In this implementation, an example in which the second connection electrode **142** electrically connects two receive modules **141** is used. The second connection electrode **142** and the receive electrode **140** are located at a same layer.

[0118] This application further provides a touchscreen. FIG. 21 is a schematic sectional view of the touchscreen. The touchscreen includes a light-emitting layer **300**, a packaging layer **400**, and the touch film described in any one of the foregoing implementations. The light-emitting layer **300**, the packaging layer **400**, and the touch film are sequentially stacked. The touch film includes a touch electrode layer **100** and a dielectric isolation layer **200**. The dielectric isolation layer **200** is attached to the packaging layer **400**. The touch electrode layer **100** is located in the dielectric isolation layer **200**.

[0119] The light-emitting layer **300** may be an OLED flexible light-emitting layer, and includes a pixel definition layer **310**. There are a plurality of pixels **311** on the pixel definition layer **310**. FIG. 22 is a relative schematic diagram of a touch electrode layer and pixels.

[0120] The pixels **311** are in a one-to-one correspondence with a plurality of mesh units **120** in the touch electrode layer **100** in a light-emitting direction of the light-emitting layer **300**. Specifically, the light-emitting direction of the light-emitting layer **300** is a direction indicated by an arrow in FIG. 17. Light emitted by each pixel **311** diverges outward through a mesh unit **120** corresponding to the pixel **311**. Different mesh units **120** correspond to pixels **311** of a same color or different colors.

[0121] According to the touchscreen in this implementation, the touch film is packaged and integrated on the light-emitting layer **300** by using a thin film, and the packaging layer **400** and the touch film are disposed on the OLED flexible light-emitting layer, to form a flexible touchscreen that can be bent reciprocally. In addition, a transmit electrode **130** and a receive electrode **140** of the touch electrode layer **100** in the touch film are provided with fractures **111** at vertex angles of the mesh units **120**, and formed touch capacitor structures are located at the vertex angles of the mesh units. When the touchscreen is subject to an external pressing force or is bent, a stress value at positions of the fractures **111** is correspondingly reduced, and the dielectric isolation layer filled in the fractures **111** can withstand a greater stress without deformation. This improves structural strength of the touchscreen, and prolongs a service life of the flexible touchscreen.

[0122] In a possible implementation, as shown in FIG. 22 and FIG. 23, FIG. 23 is an enlarged diagram of a part IV in FIG. 21, and a projection of each pixel **311** on the touch electrode layer **100** in the light-emitting direction (refer to the direction indicated by the arrow in FIG. 23) of the light-emitting layer **300** falls within a mesh unit **120** corresponding to the pixel **311**.

[0123] As shown in FIG. 23, a projection of a pixel **311** in the light-emitting direction of the light-

emitting layer **300** on a plane on which the touch electrode layer **100** is located is a region between two dashed lines. A part between two metal lines **110** shown in FIG. **23** corresponds to one mesh unit **120**. There is a gap between the projection of the pixel **311** on the plane on which the touch electrode layer **100** is located and each metal line **110**, so that light emitted by the pixel **311** in the light-emitting direction passes through the mesh unit **120** without being blocked by the metal lines **110**.

[0124] Specifically, a spacing between two adjacent pixels **311** is greater than a width of the metal line **110**. FIG. **24** is an enlarged diagram of a part V in FIG. **22**. The spacing between two adjacent pixels **311** is $L1$, the width of the metal line **110** is $L2$, and a value of the spacing $L1$ is greater than a value of the width $L2$. Therefore, when the touchscreen is compared from a top view, there is a spacing between edges of each pixel **311** and the metal lines **110** around the pixel **311**, and an area of the pixel **311** is less than an area of the mesh unit **120**.

[0125] Specifically, a first plane is a plane perpendicular to the light-emitting direction of the light-emitting layer **300**. For example, a plane in which graphics in FIG. **22** and FIG. **24** are located is the first plane. Along the first plane, a spacing between the metal line **110** and the edge of the pixel **311** is within a range of 1 micrometer to 10 micrometers, to ensure that the light emitted by the pixel **311** can pass through the mesh unit **120** to a large extent without being blocked by the metal line **110**.

[0126] For example, on the plane shown in FIG. **24**, a spacing between the metal line **110** and the edge of the pixel **311** is a vertical distance between a point on the edge of the pixel **311** and an edge of the metal line **110**, for example, a distance $L3$ shown in FIG. **24**. In an actual touchscreen product, the spacing is a vertical distance between a point on an edge of the projection of the pixel **311** in the light-emitting direction on the first plane and the edge of the metal line **110**.

[0127] This application further provides an electronic device, including a display screen. The display screen includes the touchscreen described in any one of the foregoing implementations. The electronic device may be a terminal device such as a mobile phone, a tablet computer, or a PC. A main application scenario of the electronic device described in this application is to reduce a probability of a touch failure of a screen in a process of bending and using the device. For example, as shown in FIG. **1** and FIG. **2**, the electronic device may be a foldable mobile phone, the foldable mobile phone includes the display screen, and the display screen is a flexible foldable display screen.

[0128] In this application, electrode fractures of a touch film in the electronic device are provided at vertex angles of mesh units. When a touchscreen of a bent part of the foldable mobile phone is bent, a stress concentration factor at positions of the fractures is effectively reduced, so that a possibility of a fracture at a dielectric isolation layer of the touchscreen due to a stress concentration is reduced. This reduces a probability of a failure of a touch function and the screen, and prolongs a service life of the display screen.

[0129] The foregoing embodiments are merely intended to describe the technical solutions of this application, but not to limit this application. Although this application is described in detail with reference to the foregoing embodiments, persons of ordinary skill in the art should understand that they may still make modifications to the technical solutions described in the foregoing embodiments or make equivalent replacements to some technical features thereof, without departing from the spirit and scope of the technical solutions of embodiments of this application, all of which shall fall within the protection scope of this application.

Claims

1. An electronic device, comprises a touchscreen, wherein the touchscreen comprises a light-emitting layer, a packaging layer, and a touch film, wherein the touch film, the packaging layer, and the light-emitting layer are sequentially stacked, wherein the touch film comprises a touch

electrode layer and a dielectric isolation layer, wherein the touch electrode layer is located in the dielectric isolation layer, the touch electrode layer comprises a metal lines arranged in a cross manner to form a plurality of mesh units; a plurality of fractures are provided on the metal lines, the plurality of fractures are configured to divide the metal lines into a transmit electrode and a receive electrode, and the transmit electrode and the receive electrode form a touch capacitor structure at each fracture of the fractures; and a first direction is perpendicular to a conduction direction of each fracture, each of two ends of the corresponding fracture in the first direction is adjacent to two sides of at least one of the mesh units, and the corresponding fracture is configured to electrically isolate mesh units on two sides in the conduction direction of the fracture.

2. The electronic device according to claim 1, wherein the fractures comprise first fractures, each of the first fractures is located between opposite vertex angles of at least two diagonally adjacent mesh units, the corresponding fracture is adjacent to the vertex angles, and a width of the corresponding first fracture in the first direction is within a range of 1 micrometer to 10 micrometers.

3. The electronic device according to claim 1, wherein the mesh units comprise first mesh units, the first mesh units are located at an edge of at least one of the transmit electrode or the receive electrode, and at least one vertex angle of each of the first mesh units is adjacent to the fractures.

4. The electronic device according to claim 1, wherein the mesh units comprise second mesh units, and side metal lines of the second mesh units are isolated from the fractures.

5. The electronic device according to claim 1, wherein the mesh units comprise third mesh units, the third mesh units are communicated with the fractures, and adjacent third mesh units are communicably coupled to each other.

6. The electronic device according to claim 1, wherein the transmit electrode comprises transmit modules, the receive electrode comprises receive modules, one or more the transmit modules and one or more of the receive modules are disposed in a staggered manner, a receive module is disposed between one or more pairs of adjacent transmit modules, the touch electrode layer comprises a first metal bridge, and the first metal bridge electrically connects at least two of the transmit modules.

7. The electronic device according to claim 6, wherein the first metal bridge spans one side of the receive module and is electrically connected to the adjacent transmit modules, and the receive module between the adjacent transmit modules is electrically isolated from the first metal bridge.

8. The electronic device according to claim 1, wherein the transmit electrode comprises a plurality of transmit modules, the receive electrode comprises a plurality of receive modules, one or more of the transmit modules and one or more of the receive modules are disposed in a staggered manner, a transmit module between one or more pairs of adjacent receive modules, the touch electrode layer comprises a second metal bridge, and the second metal bridge electrically connects one or more of the receive modules.

9. The electronic device according to claim 8, wherein the second metal bridge spans one side of the transmit module and is electrically connected to the adjacent receive modules, and the transmit module between the adjacent receive modules is electrically isolated from the second metal bridge.

10. The electronic device according to claim 1, wherein the transmit electrode and the receive electrode are in different layers in the dielectric isolation layer.

11. The electronic device according to claim 10, wherein the touch electrode layer comprises a first connection electrode, the transmit electrode comprises a transmit modules, the first connection electrode electrically connects at least two of the transmit modules, and the first connection electrode and the transmit electrode are located at a same layer.

12. The electronic device according to claim 10, wherein the touch electrode layer comprises a second connection electrode, the receive electrode comprises a receive modules, the second connection electrode electrically connects at least two of the receive modules, and the second connection electrode and the receive electrode are located at a same layer.

13. (canceled)

14. The electronic device according to claim 1, wherein the light-emitting layer comprises a pixel definition layer, the pixel definition layer comprises a plurality of pixels, the plurality of pixels are arranged in a matrix manner, and the plurality of pixels are in a one-to-one correspondence with a plurality of mesh units in a light-emitting direction of the light-emitting layer.

15. The electronic device according to claim 1, wherein a projection of each pixel on a touch electrode layer in the light-emitting direction of the light-emitting layer falls within a mesh unit corresponding to the pixel, and a gap exists between a side metal line of the mesh unit and the projection that falls within the mesh unit.

16. The electronic device according to claim 1, wherein a spacing between adjacent pixels is greater than a width of a metal line of the metal lines.

17. The electronic device according to claim 1, wherein a first plane is perpendicular to the light-emitting direction of the light-emitting layer, and a spacing between the metal line and an edge of a pixel is within a range of 1 micrometer to 10 micrometers along the first plane.

18. The electronic device according to claim 1, wherein the light-emitting layer comprises an OLED light-emitting layer.

19. (canceled)

20. The electronic device according to claim 1, wherein the electronic device comprises a foldable mobile phone, the foldable mobile phone comprises a display screen, and the display screen is a flexible foldable display screen.

21. The electronic device according to claim 2, wherein the transmit electrode comprises transmit modules, the receive electrode comprises receive modules, one or more of the transmit modules and one or more of the receive modules are disposed in a staggered manner, a receive module is disposed between one or more pairs of adjacent transmit modules, the touch electrode layer comprises a first metal bridge, and the first metal bridge electrically connects at least two of the transmit modules.
