

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12400419
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Metuki; Assaf et al.

Single read of keypoint descriptors of image from system memory for efficient header matching

Abstract

Embodiments of the present disclosure relate to sequentially loading keypoint descriptors of a previous image and comparing them with a plurality of keypoint descriptors of a current image. The keypoint descriptors of the previous image are stored and accessed from a system memory while the keypoint descriptors of the current image are stored and accessed from a local memory. Hence, the keypoint descriptors of the previous image are received only once at a descriptor match circuit while the keypoint descriptors of the current image are received multiple times for comparison against different keypoint descriptors of the previous image.

Inventors: Metuki; Assaf (Moshav Herut, IL), Gal; Danny (Hod-Hasharon, IL), Fishel; Liran (Raanana, IL)

Applicant: Apple Inc. (Cupertino, CA)

Family ID: 1000008779424

Assignee: APPLE INC. (Cupertino, CA)

Appl. No.: 17/695038

Filed: March 15, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230298302 A1	Sep. 21, 2023

Publication Classification

Int. Cl.: G06V10/46 (20220101); G06V10/74 (20220101); G06V10/75 (20220101); G06V10/94 (20220101)

U.S. Cl.:

CPC **G06V10/46** (20220101); **G06V10/751** (20220101); **G06V10/761** (20220101);
G06V10/94 (20220101);

Field of Classification Search

CPC: G06V (10/46); G06V (10/751); G06V (10/761); G06V (10/94); G06V (10/462); G06V (10/757)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9229956	12/2015	Ke et al.	N/A	N/A
9665790	12/2016	Gutelzon et al.	N/A	N/A
9672409	12/2016	Jonsson et al.	N/A	N/A
10671892	12/2019	Daskalov	N/A	G06F 18/217
2003/0016235	12/2002	Odagawa	345/629	G06T 11/60
2014/0201200	12/2013	Li et al.	N/A	N/A
2014/0334688	12/2013	Saito	382/107	H04N 19/436
2014/0369562	12/2013	Saito	382/103	G06T 7/20
2019/0333183	12/2018	Neela	N/A	G06T 1/60
2020/0065986	12/2019	Chen	N/A	H04N 23/80
2020/0401617	12/2019	Spiegel	N/A	G06F 16/587
2022/0150403	12/2021	Wu	N/A	G06F 1/1686
2022/0262035	12/2021	Liu	N/A	G06T 7/0002
2023/0298302	12/2022	Metuki	382/100	G06V 10/462
2023/0306541	12/2022	Bykau	N/A	G06F 16/583
2023/0316706	12/2022	Metuki	382/181	G06V 10/757

OTHER PUBLICATIONS

Alahi et al., "FREAK: Fast Retina Keypoint", IEEE, 2012 (Year: 2012). cited by examiner

Primary Examiner: Carter; Aaron W

Attorney, Agent or Firm: Sterne, Kessler, Goldstein & Fox P.L.L.C.

Background/Summary

BACKGROUND

1. Field of the Disclosure

(1) The present disclosure relates to a circuit for processing images and more specifically to determining matching keypoints in images.

2. Description of the Related Arts

(2) Image data captured by an image sensor or received from other data sources is often processed in an image processing pipeline before further processing or consumption. For example, raw image

data may be corrected, filtered, or otherwise modified before being provided to subsequent components such as a video encoder. To perform corrections or enhancements for captured image data, various components, unit stages or modules may be employed.

(3) Such an image processing pipeline may be structured so that corrections or enhancements to the captured image data can be performed in an expedient way without consuming other system resources. Although many image processing algorithms may be performed by executing software programs on central processing unit (CPU), execution of such programs on the CPU would consume significant bandwidth of the CPU and other peripheral resources as well as increase power consumption. Hence, image processing pipelines are implemented as a hardware component separate from the CPU and dedicated to perform one or more image processing algorithms.

(4) Some processing of image data involves detecting of keypoints in the images. Keypoints are distinctive features in an image, and are associated with corresponding descriptors. Determining matching of keypoints in different images are typically performed by the CPU. Based on detected keypoints, various subsequent operations such as warping of images may be performed.

SUMMARY

(5) Embodiments relate to determining matching keypoints in the image by reduce accesses to an external memory to receive keypoint descriptors. A first local memory receives first keypoint descriptors of a first image from the external memory and stores the received first keypoint descriptors. A second local memory receives second keypoint descriptors of a second image and stores the received second keypoint descriptors. The second local memory has a faster access speed than the external memory. A header match circuit sequentially receives each of headers of the first keypoint descriptors, and determines whether each of the headers of the first keypoint descriptors and a corresponding plurality of headers of the second keypoint descriptors satisfy one or more match criteria.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a high-level diagram of an electronic device, according to one embodiment

(2) FIG. 2 is a block diagram illustrating components in the electronic device, according to one embodiment.

(3) FIG. 3 is a block diagram illustrating image processing pipelines implemented using an image signal processor, according to one embodiment.

(4) FIG. 4 is a block diagram illustrating a vision module of the image signal processor, according to one embodiment.

(5) FIG. 5 is a block diagram of a descriptor match circuit of the vision module, according to one embodiment.

(6) FIG. 6 is a block diagram of keypoint descriptors stored in a current descriptor memory of the descriptor match circuit, according to one embodiment.

(7) FIGS. 7A and 7B are conceptual diagrams illustrating operations performed by a header match circuit of the descriptor match circuit, according to one embodiment.

(8) FIG. 8 is a flowchart illustrating a method for determining matching keypoints in two images, according to one embodiment.

(9) The figures depict, and the detail description describes, various non-limiting embodiments for purposes of illustration only.

DETAILED DESCRIPTION

(10) Reference will now be made in detail to embodiments, examples of which are illustrated in the accompanying drawings. In the following detailed description, numerous specific details are set forth in order to provide a thorough understanding of the various described embodiments.

However, the described embodiments may be practiced without these specific details. In other instances, well-known methods, procedures, components, circuits, and networks have not been described in detail so as not to unnecessarily obscure aspects of the embodiments.

(11) Embodiments of the present disclosure relate to sequentially loading keypoint descriptors of a previous image and comparing them with a plurality of keypoint descriptors of a current image. The keypoint descriptors of the previous image are stored and accessed from a system memory while the keypoint descriptors of the current image are stored and accessed from a local memory. Hence, the keypoint descriptors of the previous image are received only once at a descriptor match circuit while the keypoint descriptors of the current image are received multiple times for comparison against different keypoint descriptors of the previous image.

(12) Exemplary Electronic Device

(13) Embodiments of electronic devices, user interfaces for such devices, and associated processes for using such devices are described. In some embodiments, the device is a portable communications device, such as a mobile telephone, that also contains other functions, such as personal digital assistant (PDA) and/or music player functions. Exemplary embodiments of portable multifunction devices include, without limitation, the iPhone®, iPod Touch®, Apple Watch®, and iPad® devices from Apple Inc. of Cupertino, California. Other portable electronic devices, such as wearables, laptops or tablet computers, are optionally used. In some embodiments, the device is not a portable communications device, but is a desktop computer or other computing device that is not designed for portable use. In some embodiments, the disclosed electronic device may include a touch sensitive surface (e.g., a touch screen display and/or a touch pad). An example electronic device described below in conjunction with FIG. 1 (e.g., device **100**) may include a touch-sensitive surface for receiving user input. The electronic device may also include one or more other physical user-interface devices, such as a physical keyboard, a mouse and/or a joystick.

(14) FIG. 1 is a high-level diagram of an electronic device **100**, according to one embodiment. Device **100** may include one or more physical buttons, such as a “home” or menu button **104**. Menu button **104** is, for example, used to navigate to any application in a set of applications that are executed on device **100**. In some embodiments, menu button **104** includes a fingerprint sensor that identifies a fingerprint on menu button **104**. The fingerprint sensor may be used to determine whether a finger on menu button **104** has a fingerprint that matches a fingerprint stored for unlocking device **100**. Alternatively, in some embodiments, menu button **104** is implemented as a soft key in a graphical user interface (GUI) displayed on a touch screen.

(15) In some embodiments, device **100** includes touch screen **150**, menu button **104**, push button **106** for powering the device on/off and locking the device, volume adjustment buttons **108**, Subscriber Identity Module (SIM) card slot **110**, head set jack **112**, and docking/charging external port **124**. Push button **106** may be used to turn the power on/off on the device by depressing the button and holding the button in the depressed state for a predefined time interval; to lock the device by depressing the button and releasing the button before the predefined time interval has elapsed; and/or to unlock the device or initiate an unlock process. In an alternative embodiment, device **100** also accepts verbal input for activation or deactivation of some functions through microphone **113**. The device **100** includes various components including, but not limited to, a memory (which may include one or more computer readable storage mediums), a memory controller, one or more central processing units (CPUs), a peripherals interface, an RF circuitry, an audio circuitry, speaker **111**, microphone **113**, input/output (I/O) subsystem, and other input or control devices. Device **100** may include one or more image sensors **164**, one or more proximity sensors **166**, and one or more accelerometers **168**. Device **100** may include more than one type of image sensors **164**. Each type may include more than one image sensor **164**. For example, one type of image sensors **164** may be cameras and another type of image sensors **164** may be infrared sensors that may be used for face recognition. In addition, or alternatively, the image sensors **164** may be associated with different lens configuration. For example, device **100** may include rear

image sensors, one with a wide-angle lens and another with as a telephoto lens. The device **100** may include components not shown in FIG. **1** such as an ambient light sensor, a dot projector and a flood illuminator.

(16) Device **100** is only one example of an electronic device, and device **100** may have more or fewer components than listed above, some of which may be combined into a component or have a different configuration or arrangement. The various components of device **100** listed above are embodied in hardware, software, firmware or a combination thereof, including one or more signal processing and/or application specific integrated circuits (ASICs). While the components in FIG. **1** are shown as generally located on the same side as the touch screen **150**, one or more components may also be located on an opposite side of device **100**. For example, the front side of device **100** may include an infrared image sensor **164** for face recognition and another image sensor **164** as the front camera of device **100**. The back side of device **100** may also include additional two image sensors **164** as the rear cameras of device **100**.

(17) FIG. **2** is a block diagram illustrating components in device **100**, according to one embodiment. Device **100** may perform various operations including image processing. For this and other purposes, the device **100** may include, among other components, image sensor **202**, system-on-a chip (SOC) component **204**, system memory **230**, persistent storage (e.g., flash memory) **228**, orientation sensor **234**, and display **216**. The components as illustrated in FIG. **2** are merely illustrative. For example, device **100** may include other components (such as speaker or microphone) that are not illustrated in FIG. **2**. Further, some components (such as orientation sensor **234**) may be omitted from device **100**.

(18) Image sensors **202** are components for capturing image data. Each of the image sensors **202** may be embodied, for example, as a complementary metal-oxide-semiconductor (CMOS) active-pixel sensor, a camera, video camera, or other devices. Image sensors **202** generate raw image data that is sent to SOC component **204** for further processing. In some embodiments, the image data processed by SOC component **204** is displayed on display **216**, stored in system memory **230**, persistent storage **228** or sent to a remote computing device via network connection. The raw image data generated by image sensors **202** may be in a Bayer color filter array (CFA) pattern (hereinafter also referred to as “Bayer pattern”). An image sensor **202** may also include optical and mechanical components that assist image sensing components (e.g., pixels) to capture images. The optical and mechanical components may include an aperture, a lens system, and an actuator that controls the lens position of the image sensor **202**.

(19) Motion sensor **234** is a component or a set of components for sensing motion of device **100**. Motion sensor **234** may generate sensor signals indicative of orientation and/or acceleration of device **100**. The sensor signals are sent to SOC component **204** for various operations such as turning on device **100** or rotating images displayed on display **216**.

(20) Display **216** is a component for displaying images as generated by SOC component **204**. Display **216** may include, for example, liquid crystal display (LCD) device or an organic light emitting diode (OLED) device. Based on data received from SOC component **204**, display **216** may display various images, such as menus, selected operating parameters, images captured by image sensor **202** and processed by SOC component **204**, and/or other information received from a user interface of device **100** (not shown).

(21) System memory **230** is a component for storing instructions for execution by SOC component **204** and for storing data processed by SOC component **204**. System memory **230** may be embodied as any type of memory including, for example, dynamic random access memory (DRAM), synchronous DRAM (SDRAM), double data rate (DDR, DDR2, DDR3, etc.) RAMBUS DRAM (RDRAM), static RAM (SRAM) or a combination thereof. In some embodiments, system memory **230** may store pixel data or other image data or statistics in various formats.

(22) Persistent storage **228** is a component for storing data in a non-volatile manner. Persistent storage **228** retains data even when power is not available. Persistent storage **228** may be embodied

as read-only memory (ROM), flash memory or other non-volatile random access memory devices. (23) SOC component **204** is embodied as one or more integrated circuit (IC) chip and performs various data processing processes. SOC component **204** may include, among other subcomponents, image signal processor (ISP) **206**, a central processor unit (CPU) **208**, a network interface **210**, motion sensor interface **212**, display controller **214**, graphics processor (GPU) **220**, memory controller **222**, video encoder **224**, storage controller **226**, and various other input/output (I/O) interfaces **218**, and bus **232** connecting these subcomponents. SOC component **204** may include more or fewer subcomponents than those shown in FIG. 2.

(24) ISP **206** is hardware that performs various stages of an image processing pipeline. In some embodiments, ISP **206** may receive raw image data from image sensor **202**, and process the raw image data into a form that is usable by other subcomponents of SOC component **204** or components of device **100**. ISP **206** may perform various image-manipulation operations such as image translation operations, horizontal and vertical scaling, color space conversion and/or image stabilization transformations, as described below in detail with reference to FIG. 3.

(25) CPU **208** may be embodied using any suitable instruction set architecture, and may be configured to execute instructions defined in that instruction set architecture. CPU **208** may be general-purpose or embedded processors using any of a variety of instruction set architectures (ISAs), such as the x86, PowerPC, SPARC, RISC, ARM or MIPS ISAs, or any other suitable ISA. Although a single CPU is illustrated in FIG. 2, SOC component **204** may include multiple CPUs. In multiprocessor systems, each of the CPUs may commonly, but not necessarily, implement the same ISA.

(26) Graphics processing unit (GPU) **220** is graphics processing circuitry for performing graphical data. For example, GPU **220** may render objects to be displayed into a frame buffer (e.g., one that includes pixel data for an entire frame). GPU **220** may include one or more graphics processors that may execute graphics software to perform a part or all of the graphics operation, or hardware acceleration of certain graphics operations.

(27) I/O interfaces **218** are hardware, software, firmware or combinations thereof for interfacing with various input/output components in device **100**. I/O components may include devices such as keypads, buttons, audio devices, and sensors such as a global positioning system. I/O interfaces **218** process data for sending data to such I/O components or process data received from such I/O components.

(28) Network interface **210** is a subcomponent that enables data to be exchanged between devices **100** and other devices via one or more networks (e.g., carrier or agent devices). For example, video or other image data may be received from other devices via network interface **210** and be stored in system memory **230** for subsequent processing (e.g., via a back-end interface to image signal processor **206**, such as discussed below in FIG. 3) and display. The networks may include, but are not limited to, Local Area Networks (LANs) (e.g., an Ethernet or corporate network) and Wide Area Networks (WANs). The image data received via network interface **210** may undergo image processing processes by ISP **206**.

(29) Motion sensor interface **212** is circuitry for interfacing with motion sensor **234**. Motion sensor interface **212** receives sensor information from motion sensor **234** and processes the sensor information to determine the orientation or movement of the device **100**.

(30) Display controller **214** is circuitry for sending image data to be displayed on display **216**. Display controller **214** receives the image data from ISP **206**, CPU **208**, graphic processor or system memory **230** and processes the image data into a format suitable for display on display **216**.

(31) Memory controller **222** is circuitry for communicating with system memory **230**. Memory controller **222** may read data from system memory **230** for processing by ISP **206**, CPU **208**, GPU **220** or other subcomponents of SOC component **204**. Memory controller **222** may also write data to system memory **230** received from various subcomponents of SOC component **204**.

(32) Video encoder **224** is hardware, software, firmware or a combination thereof for encoding

video data into a format suitable for storing in persistent storage **128** or for passing the data to network interface **w10** for transmission over a network to another device.

(33) In some embodiments, one or more subcomponents of SOC component **204** or some functionality of these subcomponents may be performed by software components executed on ISP **206**, CPU **208** or GPU **220**. Such software components may be stored in system memory **230**, persistent storage **228** or another device communicating with device **100** via network interface **210**.

(34) Image data or video data may flow through various data paths within SOC component **204**. In one example, raw image data may be generated from the image sensors **202** and processed by ISP **206**, and then sent to system memory **230** via bus **232** and memory controller **222**. After the image data is stored in system memory **230**, it may be accessed by video encoder **224** for encoding or by display **116** for displaying via bus **232**.

(35) In another example, image data is received from sources other than the image sensors **202**. For example, video data may be streamed, downloaded, or otherwise communicated to the SOC component **204** via wired or wireless network. The image data may be received via network interface **210** and written to system memory **230** via memory controller **222**. The image data may then be obtained by ISP **206** from system memory **230** and processed through one or more image processing pipeline stages, as described below in detail with reference to FIG. 3. The image data may then be returned to system memory **230** or be sent to video encoder **224**, display controller **214** (for display on display **216**), or storage controller **226** for storage at persistent storage **228**.

(36) Example Image Signal Processing Pipelines

(37) FIG. 3 is a block diagram illustrating image processing pipelines implemented using ISP **206**, according to one embodiment. In the embodiment of FIG. 3, ISP **206** is coupled to an image sensor system **201** that includes one or more image sensors **202A** through **202N** (hereinafter collectively referred to as “image sensors **202**” or also referred individually as “image sensor **202**”) to receive raw image data. The image sensor system **201** may include one or more sub-systems that control the image sensors **202** individually. In some cases, each image sensor **202** may operate independently while, in other cases, the image sensors **202** may share some components. For example, in one embodiment, two or more image sensors **202** may share the same circuit board that controls the mechanical components of the image sensors (e.g., actuators that change the lens positions of each image sensor). The image sensing components of an image sensor **202** may include different types of image sensing components that may provide raw image data in different forms to the ISP **206**. For example, in one embodiment, the image sensing components may include focus pixels that are used for auto-focusing and image pixels that are used for capturing images. In another embodiment, the image sensing pixels may be used for both auto-focusing and image capturing purposes.

(38) ISP **206** implements an image processing pipeline which may include a set of stages that process image information from creation, capture or receipt to output. ISP **206** may include, among other components, sensor interface **302**, central control **320**, front-end pipeline stages **330**, back-end pipeline stages **340**, image statistics module **304**, vision module **322**, back-end interface **342**, output interface **316**, and auto-focus circuits **350A** through **350N** (hereinafter collectively referred to as “auto-focus circuits **350**” or referred individually as “auto-focus circuits **350**”). ISP **206** may include other components not illustrated in FIG. 3 or may omit one or more components illustrated in FIG. 3.

(39) In one or more embodiments, different components of ISP **206** process image data at different rates. In the embodiment of FIG. 3, front-end pipeline stages **330** (e.g., raw processing stage **306** and resample processing stage **308**) may process image data at an initial rate. Thus, the various different techniques, adjustments, modifications, or other processing operations performed by these front-end pipeline stages **330** at the initial rate. For example, if the front-end pipeline stages **330** process 2 pixels per clock cycle, then raw processing stage **306** operations (e.g., black level compensation, highlight recovery and defective pixel correction) may process 2 pixels of image

data at a time. In contrast, one or more back-end pipeline stages **340** may process image data at a different rate less than the initial data rate. For example, in the embodiment of FIG. 3, back-end pipeline stages **340** (e.g., noise processing stage **310**, color processing stage **312**, and output rescale **314**) may be processed at a reduced rate (e.g., 1 pixel per clock cycle).

(40) Raw image data captured by image sensors **202** may be transmitted to different components of ISP **206** in different manners. In one embodiment, raw image data corresponding to the focus pixels may be sent to the auto-focus circuits **350** while raw image data corresponding to the image pixels may be sent to the sensor interface **302**. In another embodiment, raw image data corresponding to both types of pixels may simultaneously be sent to both the auto-focus circuits **350** and the sensor interface **302**.

(41) Auto-focus circuits **350** may include hardware circuit that analyzes raw image data to determine an appropriate lens position of each image sensor **202**. In one embodiment, the raw image data may include data that is transmitted from image sensing pixels that specializes in image focusing. In another embodiment, raw image data from image capture pixels may also be used for auto-focusing purpose. An auto-focus circuit **350** may perform various image processing operations to generate data that determines the appropriate lens position. The image processing operations may include cropping, binning, image compensation, scaling to generate data that is used for auto-focusing purpose. The auto-focusing data generated by auto-focus circuits **350** may be fed back to the image sensor system **201** to control the lens positions of the image sensors **202**. For example, an image sensor **202** may include a control circuit that analyzes the auto-focusing data to determine a command signal that is sent to an actuator associated with the lens system of the image sensor to change the lens position of the image sensor. The data generated by the auto-focus circuits **350** may also be sent to other components of the ISP **206** for other image processing purposes. For example, some of the data may be sent to image statistics **304** to determine information regarding auto-exposure.

(42) The auto-focus circuits **350** may be individual circuits that are separate from other components such as image statistics **304**, sensor interface **302**, front-end **330** and back-end **340**. This allows the ISP **206** to perform auto-focusing analysis independent of other image processing pipelines. For example, the ISP **206** may analyze raw image data from the image sensor **202A** to adjust the lens position of image sensor **202A** using the auto-focus circuit **350A** while performing downstream image processing of the image data from image sensor **202B** simultaneously. In one embodiment, the number of auto-focus circuits **350** may correspond to the number of image sensors **202**. In other words, each image sensor **202** may have a corresponding auto-focus circuit that is dedicated to the auto-focusing of the image sensor **202**. The device **100** may perform auto focusing for different image sensors **202** even if one or more image sensors **202** are not in active use. This allows a seamless transition between two image sensors **202** when the device **100** switches from one image sensor **202** to another. For example, in one embodiment, a device **100** may include a wide-angle camera and a telephoto camera as a dual back camera system for photo and image processing. The device **100** may display images captured by one of the dual cameras and may switch between the two cameras from time to time. The displayed images may seamless transition from image data captured by one image sensor **202** to image data captured by another image sensor without waiting for the second image sensor **202** to adjust its lens position because two or more auto-focus circuits **350** may continuously provide auto-focus data to the image sensor system **201**.

(43) Raw image data captured by different image sensors **202** may also be transmitted to sensor interface **302**. Sensor interface **302** receives raw image data from image sensor **202** and processes the raw image data into an image data processable by other stages in the pipeline. Sensor interface **302** may perform various preprocessing operations, such as image cropping, binning or scaling to reduce image data size. In some embodiments, pixels are sent from the image sensor **202** to sensor interface **302** in raster order (e.g., horizontally, line by line). The subsequent processes in the pipeline may also be performed in raster order and the result may also be output in raster order.

Although only a single image sensor and a single sensor interface **302** are illustrated in FIG. 3, when more than one image sensor is provided in device **100**, a corresponding number of sensor interfaces may be provided in ISP **206** to process raw image data from each image sensor.

(44) Front-end pipeline stages **330** process image data in raw or full-color domains. Front-end pipeline stages **330** may include, but are not limited to, raw processing stage **306** and resample processing stage **308**. A raw image data may be in Bayer raw format, for example. In Bayer raw image format, pixel data with values specific to a particular color (instead of all colors) is provided in each pixel. In an image capturing sensor, image data is typically provided in a Bayer pattern. Raw processing stage **306** may process image data in a Bayer raw format.

(45) The operations performed by raw processing stage **306** include, but are not limited, sensor linearization, black level compensation, fixed pattern noise reduction, defective pixel correction, raw noise filtering, lens shading correction, white balance gain, and highlight recovery. Sensor linearization refers to mapping non-linear image data to linear space for other processing. Black level compensation refers to providing digital gain, offset and clip independently for each color component (e.g., Gr, R, B, Gb) of the image data. Fixed pattern noise reduction refers to removing offset fixed pattern noise and gain fixed pattern noise by subtracting a dark frame from an input image and multiplying different gains to pixels. Defective pixel correction refers to detecting defective pixels, and then replacing defective pixel values. Raw noise filtering refers to reducing noise of image data by averaging neighbor pixels that are similar in brightness. Highlight recovery refers to estimating pixel values for those pixels that are clipped (or nearly clipped) from other channels. Lens shading correction refers to applying a gain per pixel to compensate for a dropoff in intensity roughly proportional to a distance from a lens optical center. White balance gain refers to providing digital gains for white balance, offset and clip independently for all color components (e.g., Gr, R, B, Gb in Bayer format). Components of ISP **206** may convert raw image data into image data in full-color domain, and thus, raw processing stage **306** may process image data in the full-color domain in addition to or instead of raw image data.

(46) Resample processing stage **308** performs various operations to convert, resample, or scale image data received from raw processing stage **306**. Operations performed by resample processing stage **308** may include, but not limited to, demosaic operation, per-pixel color correction operation, Gamma mapping operation, color space conversion and downscaling or sub-band splitting. Demosaic operation refers to converting or interpolating missing color samples from raw image data (for example, in a Bayer pattern) to output image data into a full-color domain. Demosaic operation may include low pass directional filtering on the interpolated samples to obtain full-color pixels. Per-pixel color correction operation refers to a process of performing color correction on a per-pixel basis using information about relative noise standard deviations of each color channel to correct color without amplifying noise in the image data. Gamma mapping refers to converting image data from input image data values to output data values to perform gamma correction. For the purpose of Gamma mapping, lookup tables (or other structures that index pixel values to another value) for different color components or channels of each pixel (e.g., a separate lookup table for R, G, and B color components) may be used. Color space conversion refers to converting color space of an input image data into a different format. In one embodiment, resample processing stage **308** converts RGB format into YCbCr format for further processing.

(47) Central control module **320** may control and coordinate overall operation of other components in ISP **206**. Central control module **320** performs operations including, but not limited to, monitoring various operating parameters (e.g., logging clock cycles, memory latency, quality of service, and state information), updating or managing control parameters for other components of ISP **206**, and interfacing with sensor interface **302** to control the starting and stopping of other components of ISP **206**. For example, central control module **320** may update programmable parameters for other components in ISP **206** while the other components are in an idle state. After updating the programmable parameters, central control module **320** may place these components of

ISP **206** into a run state to perform one or more operations or tasks. Central control module **320** may also instruct other components of ISP **206** to store image data (e.g., by writing to system memory **230** in FIG. 2) before, during, or after resample processing stage **308**. In this way full-resolution image data in raw or full-color domain format may be stored in addition to or instead of processing the image data output from resample processing stage **308** through backend pipeline stages **340**.

(48) Image statistics module **304** performs various operations to collect statistic information associated with the image data. The operations for collecting statistics information may include, but not limited to, sensor linearization, replace patterned defective pixels, sub-sample raw image data, detect and replace non-patterned defective pixels, black level compensation, lens shading correction, and inverse black level compensation. After performing one or more of such operations, statistics information such as 3A statistics (Auto white balance (AWB), auto exposure (AE), histograms (e.g., 2D color or component) and any other image data information may be collected or tracked. In some embodiments, certain pixels' values, or areas of pixel values may be excluded from collections of certain statistics data when preceding operations identify clipped pixels. Although only a single statistics module **304** is illustrated in FIG. 3, multiple image statistics modules may be included in ISP **206**. For example, each image sensor **202** may correspond to an individual image statistics unit **304**. In such embodiments, each statistic module may be programmed by central control module **320** to collect different information for the same or different image data.

(49) Vision module **322** performs various operations to facilitate computer vision operations at CPU **208** such as facial detection in image data. The vision module **322** may perform various operations including pre-processing, global tone-mapping and Gamma correction, vision noise filtering, resizing, keypoint detection, generation of histogram-of-orientation gradients (HOG) and normalized cross correlation (NCC). The pre-processing may include subsampling or binning operation and computation of luminance if the input image data is not in YCbCr format. Global mapping and Gamma correction can be performed on the pre-processed data on luminance image. Vision noise filtering is performed to remove pixel defects and reduce noise present in the image data, and thereby, improve the quality and performance of subsequent computer vision algorithms. Such vision noise filtering may include detecting and fixing dots or defective pixels, and performing bilateral filtering to reduce noise by averaging neighbor pixels of similar brightness. Various vision algorithms use images of different sizes and scales. Resizing of an image is performed, for example, by binning or linear interpolation operation. Keypoints are locations within an image that are surrounded by image patches well suited to matching in other images of the same scene or object. Such keypoints are useful in image alignment, computing camera pose and object tracking. Keypoint detection refers to the process of identifying such keypoints in an image. HOG provides descriptions of image patches for tasks in image analysis and computer vision. HOG can be generated, for example, by (i) computing horizontal and vertical gradients using a simple difference filter, (ii) computing gradient orientations and magnitudes from the horizontal and vertical gradients, and (iii) binning the gradient orientations. NCC is the process of computing spatial cross-correlation between a patch of image and a kernel.

(50) Back-end interface **342** receives image data from other image sources than image sensor **102** and forwards it to other components of ISP **206** for processing. For example, image data may be received over a network connection and be stored in system memory **230**. Back-end interface **342** retrieves the image data stored in system memory **230** and provides it to back-end pipeline stages **340** for processing. One of many operations that are performed by back-end interface **342** is converting the retrieved image data to a format that can be utilized by back-end processing stages **340**. For instance, back-end interface **342** may convert RGB, YCbCr 4:2:0, or YCbCr 4:2:2 formatted image data into YCbCr 4:4:4 color format.

(51) Back-end pipeline stages **340** processes image data according to a particular full-color format

(e.g., YCbCr 4:4:4 or RGB). In some embodiments, components of the back-end pipeline stages **340** may convert image data to a particular full-color format before further processing. Back-end pipeline stages **340** may include, among other stages, noise processing stage **310** and color processing stage **312**. Back-end pipeline stages **340** may include other stages not illustrated in FIG. 3.

(52) Noise processing stage **310** performs various operations to reduce noise in the image data. The operations performed by noise processing stage **310** include, but are not limited to, color space conversion, gamma/de-gamma mapping, temporal filtering, noise filtering, luma sharpening, and chroma noise reduction. The color space conversion may convert an image data from one color space format to another color space format (e.g., RGB format converted to YCbCr format). Gamma/de-gamma operation converts image data from input image data values to output data values to perform gamma correction or reverse gamma correction. Temporal filtering filters noise using a previously filtered image frame to reduce noise. For example, pixel values of a prior image frame are combined with pixel values of a current image frame. Noise filtering may include, for example, spatial noise filtering. Luma sharpening may sharpen luma values of pixel data while chroma suppression may attenuate chroma to gray (e.g., no color). In some embodiment, the luma sharpening and chroma suppression may be performed simultaneously with spatial noise filtering. The aggressiveness of noise filtering may be determined differently for different regions of an image. Spatial noise filtering may be included as part of a temporal loop implementing temporal filtering. For example, a previous image frame may be processed by a temporal filter and a spatial noise filter before being stored as a reference frame for a next image frame to be processed. In other embodiments, spatial noise filtering may not be included as part of the temporal loop for temporal filtering (e.g., the spatial noise filter may be applied to an image frame after it is stored as a reference image frame and thus the reference frame is not spatially filtered).

(53) Color processing stage **312** may perform various operations associated with adjusting color information in the image data. The operations performed in color processing stage **312** include, but are not limited to, local tone mapping, gain/offset/clip, color correction, three-dimensional color lookup, gamma conversion, and color space conversion. Local tone mapping refers to spatially varying local tone curves in order to provide more control when rendering an image. For instance, a two-dimensional grid of tone curves (which may be programmed by the central control module **320**) may be bi-linearly interpolated such that smoothly varying tone curves are created across an image. In some embodiments, local tone mapping may also apply spatially varying and intensity varying color correction matrices, which may, for example, be used to make skies bluer while turning down blue in the shadows in an image. Digital gain/offset/clip may be provided for each color channel or component of image data. Color correction may apply a color correction transform matrix to image data. 3D color lookup may utilize a three-dimensional array of color component output values (e.g., R, G, B) to perform advanced tone mapping, color space conversions, and other color transforms. Gamma conversion may be performed, for example, by mapping input image data values to output data values in order to perform gamma correction, tone mapping, or histogram matching. Color space conversion may be implemented to convert image data from one color space to another (e.g., RGB to YCbCr). Other processing techniques may also be performed as part of color processing stage **312** to perform other special image effects, including black and white conversion, sepia tone conversion, negative conversion, or solarize conversion.

(54) Output rescale module **314** may resample, transform and correct distortion on the fly as the ISP **206** processes image data. Output rescale module **314** may compute a fractional input coordinate for each pixel and uses this fractional coordinate to interpolate an output pixel via a polyphase resampling filter. A fractional input coordinate may be produced from a variety of possible transforms of an output coordinate, such as resizing or cropping an image (e.g., via a simple horizontal and vertical scaling transform), rotating and shearing an image (e.g., via non-separable matrix transforms), perspective warping (e.g., via an additional depth transform) and per-

pixel perspective divides applied in piecewise in strips to account for changes in image sensor during image data capture (e.g., due to a rolling shutter), and geometric distortion correction (e.g., via computing a radial distance from the optical center in order to index an interpolated radial gain table, and applying a radial perturbation to a coordinate to account for a radial lens distortion).

(55) Output rescale module **314** may apply transforms to image data as it is processed at output rescale module **314**. Output rescale module **314** may include horizontal and vertical scaling components. The vertical portion of the design may implement series of image data line buffers to hold the “support” needed by the vertical filter. As ISP **206** may be a streaming device, it may be that only the lines of image data in a finite-length sliding window of lines are available for the filter to use. Once a line has been discarded to make room for a new incoming line, the line may be unavailable. Output rescale module **314** may statistically monitor computed input Y coordinates over previous lines and use it to compute an optimal set of lines to hold in the vertical support window. For each subsequent line, output rescale module may automatically generate a guess as to the center of the vertical support window. In some embodiments, output rescale module **314** may implement a table of piecewise perspective transforms encoded as digital difference analyzer (DDA) steppers to perform a per-pixel perspective transformation between a input image data and output image data in order to correct artifacts and motion caused by sensor motion during the capture of the image frame. Output rescale may provide image data via output interface **316** to various other components of device **100**, as discussed above with regard to FIGS. **1** and **2**.

(56) In various embodiments, the functionality of components **302** through **350** may be performed in a different order than the order implied by the order of these functional units in the image processing pipeline illustrated in FIG. **3**, or may be performed by different functional components than those illustrated in FIG. **3**. Moreover, the various components as described in FIG. **3** may be embodied in various combinations of hardware, firmware or software.

(57) Example Vision Module Architecture for Keypoint Processing

(58) FIG. **4** is a block diagram illustrating vision module **322** of image signal processor **206**, according to one embodiment. Vision module **322** may include, among other components, a keypoint descriptor generator circuit **406**, current descriptor memory **410**, descriptor match circuit **414**, system memory access control module **422**, and local previous descriptor memory **426**. Vision module **322** may include further components not illustrated in FIG. **4**. Such components omitted include, among others, components for generating HOG and performing NCC operations.

(59) Keypoint description generator circuit **406** is a circuit that receives a version of a current image **404**, detects keypoints in the current image **404**, and generates keypoint descriptors **408** corresponding to the detected keypoints. The version of current image **404** may be a pre-processed version of an image captured by one of image sensors **202A** through **202N** or an image stored and received from system memory **230**. Keypoint descriptor generator circuit **406** may execute various keypoint detection algorithms including, but not limited to, Fast Retina Keypoint (FREAK) algorithm. Such keypoint detection and keypoint description generation are well known, and hence, description thereof is omitted herein for the sake of brevity.

(60) In one or more embodiments, keypoint descriptor generator circuit **406** may be fed with a pyramid of current image **404** for performing keypoint detection on different levels of the image pyramid. As a result of its operation, keypoint description generator circuit **406** generates the keypoint descriptors **408**. Each of the keypoint descriptors include a header and a descriptor vector.

(61) A keypoint descriptor may include a header and a descriptor vector. The header may include one or more of: (i) locations of the feature in the current or previous image, (ii) orientation angles of the keypoint, and (iii) the scale in the image pyramid where the keypoint was identified. The descriptor vector indicates comparison result on intensity of multiple patches of images at or around a corresponding keypoint.

(62) Current descriptor memory **410** is a circuit that stores keypoint descriptors **408** of keypoints in a current image, as generated by keypoint descriptor generator circuit **406**. The keypoint

descriptors **408** may be classified according to their orientation angles and stored in corresponding data bins, as described below in detail with reference to FIG. 6.

(63) Descriptor match circuit **414** receives headers and descriptor vectors of keypoint descriptors of current image **404** from current descriptor memory **410** and headers and descriptor vectors of keypoint descriptors of a previous image from local previous descriptor memory **426**, and determines a list **418** of matching keypoints in current image **404** and the previous image.

Specifically, descriptor match circuit **414** receives descriptor headers **412** of current image **404** and descriptor headers of previous image to select a subset of keypoints in current image **404** and the previous image, and then receives descriptor vectors **413**, **429** of the selected keypoints for hamming distance determination, as described below in detail with reference to FIG. 5. In one or more embodiments, list **418** include bi-directionally matched keypoints.

(64) System memory access control **422** is a circuit that controls writing or reading of keypoint descriptors to or from system memory **230**. In one or more embodiments, system memory access control **422** is embodied as a direct memory access (DMA) circuit. System memory access control **422** reads keypoint descriptors **424** of a previous image and sends keypoint descriptors **424** to local previous descriptor memory **426** for storing. Further, system memory access control **422** writes keypoint descriptors **408** of current image **404** to system memory **230** during a cycle so that these keypoint descriptors **408** may be retrieved as keypoint descriptors of a previous image in a subsequent cycle. In one or more embodiments, the data structure associated with the keypoint descriptors **408** as stored in current descriptor memory **410** is retained when copying the keypoint descriptors **408** to system memory **230**.

(65) Local previous descriptor memory **426** is a circuit that stores a predetermined number of keypoint descriptors **424** received from system memory **230** via system memory access control **422**. To reduce memory footprint, local previous description memory **426** may have a limited memory size to store fewer than the entire keypoint descriptors of the previous image. Hence, a set of keypoint descriptors fewer than a set number may be stored at a time in the local previous descriptor memory **426** for access by descriptor match circuit **414**. Furthermore, system memory access control **422** may read the same keypoint descriptors **424** of the previous image only once, as described below in detail with reference to FIGS. 7A and 7B, to reduce memory traffic associated with reading the keypoint descriptors **424** of the prior image from system memory **230**.

(66) Although current descriptor memory **410** and local previous descriptor memory **426** are described as being separate components, these memories may part of shared memory. Further, system memory access control **422** may be located outside vision module **322** and be shared with other components of ISP **206**.

(67) Example Descriptor Match Circuit Architecture

(68) FIG. 5 is a block diagram of descriptor match circuit **414** of vision module **322**, according to one embodiment. Descriptor match circuit **414** may include, among other components, header match circuit **510**, buffer **520**, distance circuit **530**, match information storage **540** and match selector circuit **550**. Descriptor match circuit **414** may include other components not illustrated in FIG. 5. The descriptor match circuit **414** first preforms comparison of headers of the keypoint descriptors, and subsequently performs distance determination for keypoints that pass the header comparison.

(69) Header match circuit **510** fetches keypoint headers **412** of the current image from current descriptor memory **410** and determines if the keypoint headers **412** satisfy one or more match criteria associated with keypoint headers **428** of the previous image. Header match circuit **510** loads a keypoint header of the previous image, and compares it against each keypoint header of the current image using one or more match criteria to determine the likelihood that the keypoints match. Header match circuit **510** sends pointers **514** to the subset of keypoints to buffer **520** for access by distance circuit **530**. Hence, only a subset of keypoints with matching counterparts are processed by distance circuit **530** for computationally intensive distance determining operations.

(70) The one or more match criteria are used to make preliminary determination on whether a keypoint of the current image is likely to match one of keypoints of the previous image. Such criteria may include, among others, (i) whether the location of the keypoint in the current image is within a spatial distance from locations of keypoints in the previous image, (ii) whether orientation angles of keypoint in the current image is within a certain range of keypoints in the previous image, (iii) whether a scale of the image pyramid of the current image at which keypoint was detected corresponds to the same scales or adjacent scales at which the keypoints in the previous image were identified, and (iv) whether the type of the keypoint in the current image (e.g., local minimum or local maximum) corresponds to the same type of keypoint in the previous image.

(71) Not all keypoint headers of the current image are loaded for header comparison a keypoint in the previous image by header match circuit **510**. To render the process of header matching more efficient, the keypoints of the current image may be classified and stored in data bins where each data bin covers a discrete range of orientation angles. When a keypoint header of the previous image is loaded onto the header match circuit **510**, only headers of keypoints of the current image having certain orientation angles are loaded onto the header match circuit **510** for header match operation.

(72) FIG. **6** is a block diagram of keypoint descriptors stored in current descriptor memory **410**, according to one embodiment. The current descriptor memory **410** may store sets of keypoint descriptors into different data bins 1 through N. Each data bin covers discrete ranges of orientation angles with a predetermined angle increment. For example, data bin 1 includes keypoint descriptors with orientation angles over 0 degrees and not over 45 degrees, data bin 2 includes keypoint descriptors with orientation angles over 45 degrees and not over 90 degrees, data bin 3 includes keypoint descriptors with orientation angles over 90 degrees and not over 135 degrees, etc.

(73) Further, each data bin may store up to a predetermined number of keypoint descriptors in a set where the predetermined number corresponds to the number of keypoint descriptors that may be stored in local previous descriptor memory **426**. In this way, the keypoint descriptors of the current image generated in a cycle may be retrieved in units of the set in a subsequent cycle where the same keypoint descriptors are used as keypoint descriptors of the previous image.

(74) After keypoint description generation circuit **406** generates a keypoint description, it is added to a set of a corresponding data bin according to its orientation angle. If a set for the generated keypoint descriptor is not available in a corresponding data bin, a new set is created to receive and store the generated keypoint descriptor. A set may hold up to a predetermined number of keypoint descriptors; and hence, when a set (e.g., set 1_1) in a data bin (e.g., data bin 1) is filled, a new set (e.g., set 1_2) is created to hold subsequent keypoint descriptors with orientation angles corresponding to the data bin (e.g., data bin 1). Not all sets may be filled, and some of the sets (e.g., set 1_A) may include fewer than the predetermined number of keypoint descriptors, and each of the data bins may have a different number of sets. The use of sets is advantageous, among other reasons, because the set can be used as a unit of keypoint generators to be later fetched for storing in local previous descriptor memory **426**, as described below in detail with reference to FIGS. **7A** and **7B**.

(75) In one or more embodiments, after a header of a descriptor of the previous image is loaded onto header match circuit **510**, header match circuit **510** determines a data bin in current descriptor memory **410** corresponding to the orientation of the loaded header of the previous frame. Header match circuit **510** then loads only the headers of the keypoint descriptors of the current image from the corresponding bin and its adjacent bins for header match operation. For example, if the header of a keypoint of a previous image loaded onto header match circuit **510** indicates an orientation angle of 50 degrees, and assuming that data bins cover orientation angles in the increments of 45 degrees (e.g., data bin 1 starts from 0 to 45 degrees, data bin 2 covers 45 to 90 degrees, etc.), only headers of keypoint descriptors in corresponding data bin (e.g., data bin 2) and headers keypoint descriptors in adjacent data bins (e.g., data bins 1 and 3) are loaded from current descriptor

memory **410** for comparison against the loaded keypoint of the previous image. In this way, fewer headers of keypoint descriptors of the current image in current descriptor memory **410** are received at header match circuit **510** and undergoes header match operations against the loaded header of previous image, which advantageously reduces the number of header matching operations in header match circuit **510**.

(76) Referring back to FIG. 5, buffer **520** receives and stores pointers **514** to a subset of keypoints in the current image and matching keypoints in the previous image based on their headers. Because the numbers of pairs of descriptors identified as potentially matching based on their headers in header match circuit **510** may not be consistent, buffer **520** temporarily stores pointers **514** of descriptors with headers that satisfy one or more criteria, and sends the pointers **514** sequentially to distance circuit **530**. In one or more embodiment, buffer **520** is implemented as a first-in, first-out (FIFO) memory.

(77) Distance circuit **530** is a circuit that determines a distance between a descriptor vector of a previous image and a descriptor vector of a current image. The distance may be, for example, a hamming distance between the descriptor vectors. The process and circuit for determining the distance of two vectors are well known in the art, and hence, their detailed description is omitted herein for the sake of brevity. Distance circuit **530** generates match information **534** as a result of its operation and stores it in match information storage **540**.

(78) For its operation, distance circuit **530** receives pointers **514** of pairs of keypoints in the current image and keypoints in the previous image using pointers **514**. After determining a distance between a descriptor vector of a first keypoint in a previous image and a descriptor vector of a second keypoint in a current image, the distance circuit **530** generates or updates a first match entry for the first keypoint and a second match entry for the second keypoint. The two match entries collectively form a part of match information **534**. The first match entry includes a field indicating a pointer to a best matching keypoint in the current image, and another field indicating the distance to the best matching keypoint in the current image. The first match entry may be updated each time the first keypoint is compared with another keypoint in the current image. Similarly, the second match entry includes a field indicating a pointer to a best matching keypoint in the previous image, and another field indicating the distance to the best matching keypoint in the previous image. Such match entries are generated and updated for each keypoints identified by pointers **514**, and stored in match information storage **540**.

(79) Match selector circuit **550** determines and outputs a list of matching pairs **418** of keypoints using match information. After distances for all pairs of keypoints in the previous image and keypoints in the current image are determined and stored in match information storage **540**, match selector circuit **550** determines keypoints of the previous image having matching keypoints in the current image by analyzing first match entries and second match entries. In one or more embodiment, match selector circuit **550** determines a bi-directionally matching pair of keypoints by identifying a keypoint of a previous image as having its first match entry indicate a keypoint of a current image as the best match, and the same keypoint of the current image as having its second match entry indicate the same keypoint of the previous image as being the best match. When the best matching keypoint of the current image from the first match entry do not match the best matching keypoint of the previous image from the second match list, these keypoints are not bi-directionally matching, and hence, they are not included in the list **418**.

(80) The list of matching pairs **418** may be used by other components of ISP **206** to process images. For example, a current image and a previous image may be warped and fused using the pairs of keypoints to generate a noise-reduced version of the current image.

(81) Example Loading and Processing of Descriptors of Previous Image

(82) FIGS. 7A and 7B are conceptual diagrams illustrating operations performed by header match circuit **510**, according to one embodiment. To reduce the data traffic associated with receiving keypoint descriptors of the previous image from system memory **230**, a keypoint descriptor of the

previous image may be received only once from system memory **230**. In one or more embodiments, a set of keypoint descriptors is received from system memory **230** as a unit where each set includes up to a predetermined number of keypoint descriptors.

(83) In FIG. 7A, set A of descriptors is illustrated as being stored in local previous descriptor memory **426**. In this example, set A includes descriptors with headers indicating orientation angles that fall within an orientation angle range that corresponds to data bin 2 (e.g., covering orientation angles over 45 degrees but not over 90 degrees). The descriptor headers of keypoints in the previous image are sequentially loaded onto previous image descriptor header space **710** of header match circuit **510**. After a header of the descriptor of the previous image is loaded onto previous image descriptor header space **710** of head match circuit **510**, header match circuit performs match compare operations using one or more criteria against all headers of the descriptors in data bins 1 through 3 of current descriptor memory **410**. Headers of descriptors in remaining data bins are not loaded onto header match circuit **510** for compare operations with the headers of descriptors in set A to reduce the number of header compare operations.

(84) Because the descriptors of the current image are all locally stored in current descriptor memory **410** within vision module **322**, the headers of the descriptors of the current image may be loaded efficiently onto header match circuit **510** multiple times for compare operations against any header of the previous image. In contrast, the descriptors of the previous image are retrieved from system memory **230** external to vision module **322**, which consumes more time and bandwidth to system memory **230**. Hence, it is advantageous to reduce the number of times the descriptors of the previous image are loaded from system memory **230** while loading the descriptors of the current image multiple times.

(85) After performing a match compare operation on last descriptor header Z in set A, set B is loaded onto local previous descriptor memory **426** as illustrated in FIG. 7B. Set B includes descriptors of the previous image with their orientation angles corresponding to an orientation angle range of data bin 4 (e.g., covering orientation angles over 135 degrees but not over 180 degrees). The headers of descriptors of the previous image are also sequentially loaded onto previous image descriptor header space **710** of header match circuit **510**, and match compare operations are performed against the headers of descriptors of data bins 3 through 5 in current descriptor memory **410**. The headers of descriptors in remaining data bins are not loaded onto header match circuit **510** for compare operations with the headers of descriptors in set B.

(86) After the last descriptor of set B is loaded onto header match circuit **510** and compared against all headers of the descriptors in data bins 3 through 5, a subsequent set of descriptors of the previous image (not shown) is loaded and repeated again until all the sets of descriptors of the previous image are processed by header match circuit **510**. Then, the process may proceed to performing match compare operations on a next image.

(87) Example Method of Comparing Headers Based on Orientation Angle Range

(88) FIG. 8 is a flowchart illustrating a method for determining matching keypoints in two images, according to one embodiment. First, first keypoint descriptors of a first image are received **810** from an external memory (e.g., system memory). The received first descriptors may be stored, for example, in local previous descriptor memory **426**.

(89) Second keypoint descriptors of a second image in a local memory (e.g., current descriptor memory **410**) are received **820**. The local memory has a faster access speed than the external memory.

(90) Each header of the first keypoint descriptors is sequentially received **830** at header match circuit **510**. The header of the first keypoint descriptors may be sent from the local previous descriptor memory **426** to header match circuit **510** sequentially.

(91) Determining is made **830** by header match circuit **510** as to whether each of the headers of the first keypoint descriptors and a corresponding plurality of headers of the second keypoint descriptors satisfy one or more match criteria.

(92) Pointers for a subset of first keypoint descriptors and a subset of the second keypoint descriptors having headers that satisfy one or more match criteria are generated by header match circuit **510** for the subsequent process of determining hamming distances between the keypoint descriptors.

(93) The processes and their sequence as described above with reference to FIG. **8** are merely illustrative. Additional processes may be added or some of the processes may be performed in parallel. For example, the process of receiving **810** the first keypoint descriptors may be performed in parallel with the process of storing **820** the second keypoint descriptors.

Claims

1. A circuit, comprising: a first local memory configured to receive first keypoint descriptors of a first image captured by an image sensor from an external memory and to store the received first keypoint descriptors; a second local memory configured to receive second keypoint descriptors of a second image captured by the image sensor subsequent to the first image and to store the received second keypoint descriptors, wherein the second keypoint descriptors are to be generated in a first cycle and copied from the second local memory to the external memory for retrieval in a second cycle subsequent to the first cycle; and a header match circuit configured to: determine that each of a plurality of headers of the first keypoint descriptors and a corresponding plurality of headers of the second keypoint descriptors satisfy one or more match criteria.
2. The circuit of claim 1, wherein the first keypoint descriptors of the first image are received from the external memory and stored in the first local memory, and wherein each of the plurality of headers of the first keypoint descriptors are received by the header match circuit from the first local memory.
3. The circuit of claim 1, wherein the first keypoint descriptors are stored in the first local memory at a same time and have orientation angles that are within a first orientation angle range.
4. The circuit of claim 3, wherein the corresponding plurality of headers of the second keypoint descriptors indicate orientation angles within a second orientation angle range broader than the first orientation angle range.
5. The circuit of claim 1, further comprising a distance circuit coupled to the header match circuit and configured to determine distances between first descriptor vectors of a subset of the first keypoint descriptors and second descriptor vectors of a subset of the second keypoint descriptors that satisfy the one or more match criteria.
6. The circuit of claim 5, wherein the header match circuit is configured to generate pointers to the subset of first keypoint descriptors and the subset of the second keypoint descriptors that satisfy the one or more match criteria, and wherein the distance circuit is configured to receive descriptor vectors of the first keypoint descriptors and the second keypoint descriptors indicated by the pointers.
7. The circuit of claim 1, wherein the second keypoint descriptors are classified into corresponding data bins in the second local memory, the data bins assigned to different orientation angle ranges that do not overlap.
8. The circuit of claim 1, further comprising a keypoint description generator circuit coupled to the second local memory and configured to generate the second keypoint descriptors by processing the second image.
9. The circuit of claim 1, wherein the first keypoint descriptors and the second keypoint descriptors comprise Fast Retina Keypoint (FREAK) descriptors.
10. A method, comprising: receiving first keypoint descriptors of a first image captured by an image sensor from an external memory; storing second keypoint descriptors of a second image captured by the image sensor subsequent to the first image in a local memory; determining that each of a plurality of headers of the first keypoint descriptors and a corresponding plurality of

headers of the second keypoint descriptors satisfy one or more match criteria; copying the second keypoint descriptors from the local memory to the external memory, wherein the second keypoint descriptors are generated in a first cycle; and retrieving the second keypoint descriptors from the external memory in a second cycle subsequent to the first cycle for comparison with third keypoint descriptors of a third image.

11. The method of claim 10, wherein the first keypoint descriptors of the first image are received from the external memory.

12. The method of claim 10, further comprising storing the received first keypoint descriptors in another local memory, wherein the first keypoint descriptors are stored in the other local memory at a same time and have orientation angles that are within a first orientation angle range.

13. The method of claim 12, wherein the corresponding plurality of headers of the second keypoint descriptors indicate orientation angles within a second orientation angle range broader than the first orientation angle range.

14. The method of claim 10, further comprising determining distances between first descriptor vectors of a subset of the first keypoint descriptors and second descriptor vectors of a subset of the second keypoint descriptors that satisfy the one or more match criteria.

15. The method of claim 14, further comprising generating pointers to the subset of first keypoint descriptors and the subset of the second keypoint descriptors that satisfy the one or more match criteria, and wherein descriptor vectors of the first keypoint descriptors and the second keypoint descriptors indicated by the pointers are processed to determine distances.

16. The method of claim 10, further comprising classifying the second keypoint descriptors into corresponding data bins for storage in a second local memory, the data bins assigned to different orientation angle ranges that do not overlap.

17. The method of claim 10, further comprising generating the second keypoint descriptors by processing the second image.

18. An electronic device, comprising: an image sensor; an external memory configured to store first keypoint descriptors of a first image captured by the image sensor; a local memory configured to store second keypoint descriptors of a second image captured by the image sensor subsequent to the first image, wherein the second keypoint descriptors are to be generated in a first cycle and copied from a second local memory to the external memory for retrieval in a second cycle subsequent to the first cycle; and a header match circuit configured to: determine that each of a plurality of headers of the first keypoint descriptors and a corresponding plurality of headers of the second keypoint descriptors satisfy one or more match criteria.

19. The electronic device of claim 18, further comprising a distance circuit coupled to the header match circuit and configured to determine distances between first descriptor vectors of a subset of the first keypoint descriptors and second descriptor vectors of a subset of the second keypoint descriptors that satisfy the one or more match criteria.

20. The electronic device of claim 19, wherein the header match circuit is further configured to generate pointers to the subset of first keypoint descriptors and the subset of the second keypoint descriptors that satisfy the one or more match criteria, and wherein the distance circuit is further configured to receive descriptor vectors of the first keypoint descriptors and the second keypoint descriptors indicated by the pointers.
