

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12416771
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Van Baelen; David Jan Irma et al.

Tray arrangements for cassettes

Abstract

A communications panel includes a chassis receiving one or more tray arrangements that each support one or more cassettes. Each cassette carries a plurality of ports at which connections are made between front and rear plug connectors. Each tray arrangement includes guides along which the cassettes slidably mount. The guides and cassettes are configured to enable cassettes of various size to mount to the same tray without reconfiguring the guides.

Inventors: Van Baelen; David Jan Irma (Winksele, BE), Pfarr; John T. (Le Sueur, MN), Wentworth; Michael J. (Belle Plaine, MN), Sievers; Scott C. (Jordan, MN), Holmberg; Matthew J. (Le Center, MN), Anderson; Jacob C. (Chanhassen, MN)

Applicant: CommScope Technologies LLC (Hickory, NC)

Family ID: 1000008820350

Assignee: COMMSCOPE TECHNOLOGIES LLC (Hickory, NC)

Appl. No.: 18/646224

Filed: April 25, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240345352 A1	Oct. 17, 2024

Related U.S. Application Data

continuation parent-doc US 17675866 20220218 US 11971598 child-doc US 18646224
us-provisional-application US 63150851 20210218

Publication Classification

Int. Cl.: G02B6/00 (20060101); **G02B6/44** (20060101)

U.S. Cl.:

CPC **G02B6/4455** (20130101); **G02B6/44526** (20230501); **G02B6/44528** (20230501);
G02B6/4453 (20130101);

Field of Classification Search

CPC: G02B (6/4453); G02B (6/4452); G02B (6/44526); G02B (6/44528); G02B (6/00)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5816863	12/1997	Reichle	N/A	N/A
6418262	12/2001	Puetz et al.	N/A	N/A
6647197	12/2002	Marrs et al.	N/A	N/A
7310471	12/2006	Bayazit et al.	N/A	N/A
7347633	12/2007	Minota	N/A	N/A
7523522	12/2008	Herring et al.	N/A	N/A
7573436	12/2008	Webb et al.	N/A	N/A
7689089	12/2009	Wagner et al.	N/A	N/A
7751674	12/2009	Hill	N/A	N/A
7945138	12/2010	Hill et al.	N/A	N/A
7962000	12/2010	Wagner et al.	N/A	N/A
7974105	12/2010	Dean, Jr. et al.	N/A	N/A
8009954	12/2010	Bran De León et al.	N/A	N/A
8059932	12/2010	Hill et al.	N/A	N/A
8226871	12/2011	Salvador et al.	N/A	N/A
8346046	12/2012	Wagner et al.	N/A	N/A
8374477	12/2012	Hill	N/A	N/A
8433171	12/2012	Cooke et al.	N/A	N/A
8452148	12/2012	Cooke et al.	N/A	N/A
8712206	12/2013	Cooke et al.	N/A	N/A
8923013	12/2013	Anderson et al.	N/A	N/A
8953924	12/2014	Cote et al.	N/A	N/A
8985862	12/2014	Cote et al.	N/A	N/A
9020320	12/2014	Cooke et al.	N/A	N/A
9134497	12/2014	Guzzo et al.	N/A	N/A
9341801	12/2015	Clatanoff et al.	N/A	N/A
9442265	12/2015	Hill et al.	N/A	N/A
9535230	12/2016	Newbury et al.	N/A	N/A
9678295	12/2016	Giraud et al.	N/A	N/A
9690064	12/2016	Sauter et al.	N/A	N/A
9690065	12/2016	Wiltjer et al.	N/A	N/A
9709765	12/2016	Wells et al.	N/A	N/A
9841574	12/2016	Pilon	N/A	N/A

9864158	12/2017	Wiltjer et al.	N/A	N/A
9910236	12/2017	Cooke et al.	N/A	N/A
10031306	12/2017	Sadasivan	N/A	G02B 6/44775
10048460	12/2017	Courchaine et al.	N/A	N/A
10054750	12/2017	Hsu et al.	N/A	N/A
10185108	12/2018	Fontaine	N/A	N/A
10215944	12/2018	Sedor et al.	N/A	N/A
10268013	12/2018	Wiltjer et al.	N/A	N/A
10281672	12/2018	Mullsteff	N/A	N/A
10317637	12/2018	Wiltjer et al.	N/A	N/A
10332429	12/2018	Pilon	N/A	N/A
10359595	12/2018	Aramayo et al.	N/A	N/A
10416406	12/2018	Ebrahimi et al.	N/A	N/A
10422971	12/2018	Cooke et al.	N/A	N/A
10429603	12/2018	Hsu	N/A	N/A
10444456	12/2018	Cooke et al.	N/A	N/A
10444457	12/2018	Lambourn	N/A	G02B 6/44528
10451828	12/2018	Ebrahimi et al.	N/A	N/A
10459184	12/2018	Cooke et al.	N/A	N/A
10493716	12/2018	Qi et al.	N/A	N/A
10514518	12/2018	Livingston et al.	N/A	N/A
10551585	12/2019	Mullsteff	N/A	N/A
10564377	12/2019	Franzke et al.	N/A	N/A
10564378	12/2019	Cooke et al.	N/A	N/A
10571640	12/2019	Berridge	N/A	N/A
10594065	12/2019	Toh et al.	N/A	N/A
10598884	12/2019	Fontaine et al.	N/A	N/A
10606013	12/2019	Wiltjer et al.	N/A	N/A
10613286	12/2019	Courchaine et al.	N/A	N/A
10641980	12/2019	Sledzinski	N/A	N/A
10656359	12/2019	Fontaine et al.	N/A	N/A
10670822	12/2019	Vogel	N/A	N/A
10698171	12/2019	Wiltjer et al.	N/A	N/A
10718919	12/2019	Courchaine et al.	N/A	N/A
10725258	12/2019	Sedor et al.	N/A	N/A
10761285	12/2019	Courchaine et al.	N/A	N/A
10768385	12/2019	Wiltjer et al.	N/A	N/A
10795107	12/2019	Pilon	N/A	N/A
10802235	12/2019	Ebrahimi et al.	N/A	N/A
10809479	12/2019	Crawford et al.	N/A	N/A
10823927	12/2019	Ebrahimi et al.	N/A	N/A
10823928	12/2019	Vogel	N/A	N/A
10845561	12/2019	Courchaine et al.	N/A	N/A
10852499	12/2019	Cooke et al.	N/A	N/A
10852501	12/2019	Livingston et al.	N/A	N/A
10928603	12/2020	Roa-Quispe et al.	N/A	N/A
10955634	12/2020	Giraud et al.	N/A	N/A
10962730	12/2020	Hill et al.	N/A	N/A

10969554	12/2020	Guzzo	N/A	N/A
11022770	12/2020	Campbell et al.	N/A	N/A
11105995	12/2020	Wiltjer et al.	N/A	N/A
11169346	12/2020	Courchaine et al.	N/A	N/A
11169347	12/2020	Vogel	N/A	N/A
11740421	12/2022	Van Baelen et al.	N/A	N/A
11971598	12/2023	Van Baelen et al.	N/A	N/A
2010/0322580	12/2009	Beamon et al.	N/A	N/A
2010/0322581	12/2009	Cooke et al.	N/A	N/A
2010/0322582	12/2009	Cooke et al.	N/A	N/A
2011/0228473	12/2010	Anderson et al.	N/A	N/A
2011/0267794	12/2010	Anderson et al.	N/A	N/A
2012/0134639	12/2011	Giraud et al.	N/A	N/A
2013/0148936	12/2012	Hill	N/A	N/A
2014/0226946	12/2013	Cooke et al.	N/A	N/A
2014/0348480	12/2013	Giraud et al.	N/A	N/A
2015/0370025	12/2014	Wells et al.	N/A	N/A
2016/0033732	12/2015	Giraud et al.	N/A	N/A
2017/0131500	12/2016	Sauter et al.	N/A	N/A
2017/0353014	12/2016	Fontaine et al.	N/A	N/A
2017/0357071	12/2016	Pilon	N/A	N/A
2018/0003913	12/2017	Takeuchi et al.	N/A	N/A
2018/0224621	12/2017	Campbell et al.	N/A	N/A
2019/0154936	12/2018	Sedor et al.	N/A	N/A
2019/0310426	12/2018	Pilon et al.	N/A	N/A
2020/0064576	12/2019	Pilon et al.	N/A	N/A
2020/0081214	12/2019	Roa-Quispe et al.	N/A	N/A
2020/0124815	12/2019	Cooke et al.	N/A	N/A
2020/0124816	12/2019	Berridge	N/A	N/A
2020/0158975	12/2019	Berridge et al.	N/A	N/A
2020/0158977	12/2019	Vogel	N/A	N/A
2020/0183090	12/2019	Pilon et al.	N/A	N/A
2020/0200988	12/2019	Vogel	N/A	N/A
2020/0209499	12/2019	Hill et al.	N/A	N/A
2020/0225434	12/2019	Ruiz	N/A	N/A
2020/0233171	12/2019	Cooke et al.	N/A	N/A
2020/0310060	12/2019	Guzzo	N/A	N/A
2020/0310061	12/2019	Livingston et al.	N/A	N/A
2020/0310064	12/2019	Crawford et al.	N/A	N/A
2020/0341223	12/2019	Sedor et al.	N/A	N/A
2020/0371304	12/2019	Wiltjer et al.	N/A	N/A
2020/0379201	12/2019	Courchaine et al.	N/A	N/A
2020/0400908	12/2019	Pilon	N/A	N/A
2021/0018711	12/2020	Courchaine et al.	N/A	N/A
2021/0080671	12/2020	Bell et al.	N/A	N/A
2021/0096317	12/2020	Ripumaree et al.	N/A	N/A
2021/0099229	12/2020	Cox et al.	N/A	N/A
2021/0116663	12/2020	Pilon et al.	N/A	N/A
2021/0140248	12/2020	Villiger et al.	N/A	N/A
2021/0173164	12/2020	Guzzo	N/A	N/A

2021/0231899	12/2020	Ye	N/A	N/A
2021/0294057	12/2020	Berridge et al.	N/A	N/A
2022/0026654	12/2021	Vogel	N/A	N/A
2022/0035113	12/2021	Courchaine et al.	N/A	N/A
2022/0196956	12/2021	Schoenfelder et al.	N/A	N/A
2023/0367090	12/2022	Van Baelen et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
286637	12/1928	CA	N/A
3 019 081	12/2018	CA	N/A
688 120	12/1996	CH	N/A
207081867	12/2017	CN	N/A
207081868	12/2017	CN	N/A
210155372	12/2019	CN	N/A
10 2015 108 528	12/2015	DE	N/A
10 2020 106 399	12/2019	DE	N/A
20 2021 104 069	12/2020	DE	N/A
0 346 613	12/1988	EP	N/A
3 361 846	12/2017	EP	N/A
3 404 461	12/2017	EP	N/A
2 888 617	12/2018	EP	N/A
3 660 564	12/2019	EP	N/A
3 660 565	12/2019	EP	N/A
2 929 388	12/2019	EP	N/A
3 767 354	12/2020	EP	N/A
2008/045994	12/2007	WO	N/A
2008/154626	12/2007	WO	N/A
2014/088981	12/2013	WO	N/A
2014/095310	12/2013	WO	N/A
2016/040548	12/2015	WO	N/A
2017/021116	12/2016	WO	N/A
2017/072022	12/2016	WO	N/A
2018/005222	12/2017	WO	N/A
2019/005479	12/2018	WO	N/A
2019/160672	12/2018	WO	N/A
2019/246181	12/2018	WO	N/A
2020/109326	12/2019	WO	N/A
2020/109327	12/2019	WO	N/A
2020/197579	12/2019	WO	N/A

OTHER PUBLICATIONS

6RU Front-Access V-Panel (FVP), Datasheet, AFL Hyperscale, 4 pages (Apr. 30, 2020). cited by applicant

ASCEND™ High Density Solutions, BRO-13084, AFL, 16 pages (Jul. 9, 2019). cited by applicant
Assembly instructions for MTP HD module support 1HE PRO, Connect Com, pp. 1-7 (Copyright Jul. 2020). cited by applicant

Centrix™ Platform, Family Spec Sheet 0230_NAFTA_AEN, Corning Optical Communications LLC, pp. 1-16 (Mar. 7, 2016). cited by applicant

CONNECTIONS 56, Specialist magazine by Reichle & De-Massari AG, pp. 1-35 (Apr. 2019). cited by applicant

Data Center Solutions, Connectivity Solutions Direct, pp. 1-3 (Sep. 2019). cited by applicant

DCX System Optical Distribution Frame, Belden Inc., pp. 1-11 (Copyright 2019). cited by applicant

EDGE8® Solutions, Spec Sheet LAN-2266-AEN, Corning Optical Communications, pp. 1-39 (Jan. 24, 2020). cited by applicant

EDGE™ and EDGE8™, LAN-1935-AEN, Corning Optical Communications, 2 pages (Jun. 2017). cited by applicant

EDGE™ Product Families, LAN-1405-AEN, Corning Optical Communications, 2 pages (May 2018). cited by applicant

EDGE™ Solutions for Enterprise Data Centers and Storage Area Networks, Spec Sheet LAN-2267-AEN, Corning Optical Communications, pp. 1-43 (Jun. 15, 2020). cited by applicant

Enhanced Management Frame (EMF), Family Spec Sheet 0168_NAFTA_AEN, Corning Optical Communications, pp. 1-26 (Nov. 17, 2016). cited by applicant

Fiber Management Systems LiSA Front Access, Edition 2015, Huber & Suhner AG, pp. 1-34 (Aug. 2015). cited by applicant

Fiber Management Systems LiSA Side Access, Edition 2015, Huber & Suhner AG, pp. 1-46 (Aug. 2015). cited by applicant

Fiber Optic System Catalogue LiSA, Edition 2014, Huber & Suhner AG, 202 pages (Aug. 2014). cited by applicant

Fiber Systems, E19 7700A, Leviton Manufacturing Co., Inc, pp. 1-15 (Admitted as prior art as of Jan. 6, 2021). cited by applicant

FVP Pre-Terminated Replacement Cassette, Datasheet, AFL Hyperscale, 3 pages (Apr. 30, 2020). cited by applicant

HD Flex Patch Panel, Installation Instructions, FS128B, Panduit Corp., pp. 1-16 (Copyright 2018). cited by applicant

HD Flex™ Fiber Cabling System Ordering Guide, FBCB45-SA-ENG Replaces FBCB29, Panduit Corp., 12 pages (Sep. 2018). cited by applicant

HD Flex™ Fiber Cabling System, FBCB46-SA-ENG replaces FBCB28, Panduit Corp., 12 pages (Nov. 2018). cited by applicant

HD Flex™ Fiber Optic Cassettes, Specification Sheet, FBSP96-WWW-ENG, Panduit Corp., 5 pages (Apr. 2018). cited by applicant

HD Flex™ Fiber Panel, Specification Sheet, FBSP120-WW-ENG, Panduit Corp., 2 pages (Copyright 2017). cited by applicant

HD82 High Density Fiber Optic Deployment Solution, Tactical Deployment Systems LLC, 14 pages (Copyright 2020). cited by applicant

International Search Report and Written Opinion for Application No. PCT/US2022/017088 mailed Jun. 7, 2022. cited by applicant

Judge, “Connectivity Solutions claims densest data center fiber,” DataCenterDynamics, 3 pages (Jan. 24, 2020). cited by applicant

N+1# Housing, 61013 rev., Connectivity Solutions Direct, 2 pages (May 2019). cited by applicant

N+1# Platform Installation Instructions, 95-100001 Rev B, Connectivity Solutions Direct, pp. 1-8 (Copyright 2020). cited by applicant

Netscale Solutions Delivering the highest 10/40/100 GbE density of any fiber solution out there, R330415/1.0d, Reichle & De-Massari AG, 20 pages (Jun. 2016). cited by applicant

Netscale-Solutions Delivering the highest fiber density, R330415/1.Oe, Reichle & De-Massari AG, 8 pages (Aug. 2016). cited by applicant

Press Release, “New Leviton Opt-X® UHDX Enclosure Meets the Demands for Maximum Density and Minimum Patching Congestion,” Leviton Manufacturing Co., Inc., 3 pages (Aug. 27,

2015). cited by applicant

Prime ODF The New Generation of Optical Distribution Systems, PRIME-ODF_01.19_EN/02.19, Reichle & De-Massari AG, 3 pages (Feb. 2019). cited by applicant

Secure Solutions Ordering Guide, LAN-1852-AEN, Corning Optical Communications, pp. 1-87 (Apr. 2020). cited by applicant

Ultra High Density (UHD) MPO Module, Datasheet, AFL Hyperscale, 5 pages (Jan. 7, 2020). cited by applicant

Ultra High Density 1U Chassis, Datasheet, AFL Hyperscale, 4 pages (Jan. 8, 2020). cited by applicant

Ultra High Density 2U Chassis, Datasheet, AFL Hyperscale, 4 pages (Mar. 20, 2020). cited by applicant

Ultra High Density Splice Module, Datasheet, AFL Hyperscale, 3 pages (Feb. 24, 2020). cited by applicant

Primary Examiner: Doan; Jennifer

Attorney, Agent or Firm: Merchant & Gould P.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of Ser. No. 17/675,866, filed Feb. 18, 2022, which claims priority from U.S. Provisional Application Ser. No. 63/150,851, filed Feb. 18, 2021, and titled “Tray Arrangements for Cassettes,” the disclosure of which is incorporated herein by reference in its entirety.

BACKGROUND

(1) In the telecommunications industry, the demand for added capacity is growing rapidly. This demand is being met in part by the increasing use and density of fiber optic transmission equipment. Even though fiber optic equipment permits higher levels of transmission in the same or smaller footprint than traditional copper transmission equipment, the demand requires even higher levels of fiber density. This has led to the development of high-density fiber handling equipment.

(2) In communications panel systems, port members (e.g., optical adapters, electrical jacks, hybrid port members, etc.) defining front ports are mounted to one or more trays that are disposable within a chassis. The front ports are configured to receive plug connectors at the fronts of the trays. The trays can either be stationary within a chassis or can slide forwardly of the chassis to enhance access to the port members.

(3) Improvements are desired.

SUMMARY

(4) A communications panel includes a chassis holding one or more trays. Each tray spans a width and depth of the chassis. In some implementations, the trays are stationary within the chassis. In other implementations, the trays are slidable within the chassis between two or more positions. Each tray is configured to support one or more cassettes carrying ports (e.g., optical ports, electrical ports, or hybrid ports) to receive plug connectors. A tray populated with one or more cassettes is referred to herein as a communications arrangement. The cassettes are slidably mounted to the tray along guides.

(5) Some aspects of the disclosure are directed to a communications arrangement including a tray carrying guides configured to slidably receive a plurality of cassettes along the guides from either the front end of the tray or from the rear end of the tray at the discretion of the user. The guides and cassettes are configured so the cassette sizes need not be in integer increments of each other. For

example, the tray may receive a first cassette having a first width and a second cassette having a second width that is 1.5 times the first width. Accordingly, the same tray can be fully populated by a plurality of cassettes having the first width or by a plurality of cassettes having the second width at the discretion of the user without modifying the guides or the tray. Alternatively, trays of different widths can be mixed on the tray.

(6) Other aspects of the disclosure are directed to a communications arrangement including a tray having parallel guides spaced apart along a lateral axis of the tray, the guides extending along a forward-rearward axis of the tray that is perpendicular to the lateral axis. One or more cassettes can be mounted to the tray to slide along the guides. Each cassette has a latching arrangement that releasably locks to a respective one of the guides. The latching arrangement includes a release handle that slides relative to the cassette along an actuation axis that is parallel to the forward-rearward axis of the tray. Pulling or pushing the release handle forwardly releases the lock between the cassette and the respective guide. Continuing to pull or push the release handle forwardly slides the cassette forwardly along the guides. Similarly, pulling or pushing the release handle rearwardly releases the lock between the cassette and the respective guide. Continuing to pull or push the release handle rearwardly slides the cassette rearwardly along the guides.

(7) Other aspects of the disclosure are directed to a communications arrangement including a tray carrying a plurality of parallel guides spaced a common distance from each other along a lateral axis of the tray. The space disposed between adjacent guides is referred to herein as a bay. One or more cassettes are mounted to the tray to slide along the guides. Each cassette spans at least two bays. Each guide is configured to inter-connect with no more than one cassette.

(8) Other aspects of the disclosure are directed to a tray carrying generally parallel guides that each define cassette engagement structure facing in a first direction. None of the guides define cassette engagement structure facing in a second direction opposite the first direction. For example, each guide may define a groove facing in the first direction and a wall facing in the second direction.

(9) Other aspects of the disclosure are directed to a cassette extending along a width between opposite first and second ends and along a length between front and rear ends. The length is orthogonal to the width. The cassette defines a bottom channel extending along the length of the cassette. In certain implementations, the cassette includes a bottom rail disposed within the bottom channel. The bottom rail extends from a base end attached to the cassette to a free end. In certain examples, the bottom rail extends parallel with the width of the cassette.

(10) Other aspects of the disclosure are directed to a cassette extending across a width between opposite first and second ends. The cassette includes an end rail at the first end. The cassette is devoid of rails at the second end. In certain implementations, the cassette defines a bottom channel extending along a depth of the cassette orthogonal to the width. In certain examples, the cassette includes a bottom rail disposed within the bottom channel. In an example, the end rail and the bottom rail of each cassette extend in a common direction from a base end to a free end.

(11) Other aspects of the disclosure are directed to a communications arrangement including a tray having parallel guides spaced apart along a lateral axis of the tray, the guides extending along a forward-rearward axis of the tray. The guides each define a notch through a top of the guide. One or more cassettes are mounted to the tray to slide along the guides. Each cassette has a latching arrangement at an end of the cassette that rides over the top of a respective one of the guides. The latching arrangement includes a stop member that drops into the notch of the respective guide to lock the cassette to the guide. The latching arrangement also includes a release handle that is actuated by moving the release handle in a different direction from the stop member. In certain examples, the release handle is moved orthogonally to the movement of the stop member. In an example, the release handle is moved along the forward-rearward axis of the tray. The release handle may extend forwardly and/or rearwardly relative to the front and rear ends of the cassette.

(12) Other aspects of the disclosure are directed to a tray arrangement extending along a lateral axis between opposite first and second ends, along a forward-rearward axis between opposite front and

rear ends, and along a height between a bottom and a top. The tray arrangement includes a tray and guides. The tray has a forward end portion towards the front end of the tray arrangement, a rearward end portion toward the rearward end of the tray arrangement, and an intermediate portion disposed between the forward end portion and the rearward end portion along the forward-rearward axis. The intermediate portion is raised along the height of the tray arrangement relative to the forward end portion. The guides are disposed at the intermediate portion and extend along the forward-rearward axis. Each of the guides is mounted to the forward end portion of the tray and to the rearward end portion of the tray. Each of the guides extends partially over the forward end portion and partially over the rearward end portion.

(13) Other aspects of the disclosure are directed to a tray arrangement extending along a lateral axis between opposite first and second ends, along a forward-rearward axis between opposite front and rear ends, and along a height between a bottom and a top. The tray arrangement includes a tray and guides. The tray has opposite top and bottom surfaces each extending along the lateral axis and the forward-rearward axis. The tray defines a main region at which a plurality of apertures are defined. Each of the apertures extends between the top and bottom surfaces. The guides are attached to the tray at the main region. Each of the guides includes a plurality of pegs extending into respective ones of the apertures defined in the tray. Each of the guides defines a grooved side facing towards the first end of the tray arrangement and a closed side facing towards the second end of the tray arrangement.

(14) Other aspects of the disclosure are directed to a tray arrangement extending along a lateral axis between opposite first and second ends, along a forward-rearward axis between opposite front and rear ends, and along a height between a bottom and a top. The tray arrangement includes a tray; and a plurality of guides mounted to the tray. Each of the guides extends along the forward-rearward axis. The guides are spaced from each other along the lateral axis. The guides include a first guide and a second guide connected by a webbing so that the first and second guides mount to the tray as a unit.

(15) Other aspects of the disclosure are directed to a method of manufacturing a plurality of tray arrangements. The method includes selecting one of a first tray arrangement and a second tray; and mounting a plurality of guides to the selected one of the first and second trays. The guides each have a plurality of pegs. The method also includes liquefying at least portions of the pegs into the countersinks. In certain implementations, each of the first and second trays defines a plurality of apertures. Each of the first and second trays define countersinks. The first tray have a different thickness than the second tray so that the apertures of the first tray have a different height than the apertures of the second tray. Mounting the guides includes inserting the pegs into the apertures of the selected one of the first and second trays. The pegs of the guides have a common size regardless of which of the first and second trays is selected.

(16) A variety of additional inventive aspects will be set forth in the description that follows. The inventive aspects can relate to individual features and to combinations of features. It is to be understood that both the forgoing general description and the following detailed description are exemplary and explanatory only and are not restrictive of the broad inventive concepts upon which the embodiments disclosed herein are based.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) The accompanying drawings, which are incorporated in and constitute a part of the description, illustrate several aspects of the present disclosure. A brief description of the drawings is as follows:

(2) FIG. 1 is a perspective view of an example communications panel system including a chassis mounted to a rack, the chassis being configured to hold a plurality of tray arrangements;

- (3) FIG. 2 is a perspective view of an example tray arrangement configured to be mounted within the chassis of FIG. 1, the tray arrangement including a tray carrying a plurality of guides;
- (4) FIG. 3 is a perspective view of the tray arrangement of FIG. 2 shown populated with a plurality of cassettes to form a communications arrangement, the cassettes each having a first width;
- (5) FIG. 4 is a perspective view of the tray arrangement of FIG. 2 shown populated with a plurality of cassettes each having a second width, the second width being about 1.5 times the first width;
- (6) FIG. 5 is a perspective view of the tray arrangement of FIG. 2 shown populated with a mixture of the cassettes of FIGS. 3 and 4;
- (7) FIG. 6 is a perspective view of the tray arrangement of FIG. 2 shown populated with a plurality of cassettes each having a third width, the third width being about double the first width;
- (8) FIG. 7 is a perspective view of the tray arrangement of FIG. 2 shown populated with a plurality of cassettes each having a fourth width, the fourth width being about triple the first width;
- (9) FIG. 8 is a perspective view of the tray arrangement of FIG. 2 showing the guides, a front extension arrangement, and a rear extension arrangement exploded outwardly from the tray;
- (10) FIG. 9 is a perspective view of the tray arrangement of FIG. 2 with the front and rear extension arrangements removed from the tray;
- (11) FIG. 10 is a side elevational view of the tray arrangement of FIG. 9;
- (12) FIG. 11 is a perspective view showing a first side of an example guide suitable for use with the tray arrangement of FIG. 2;
- (13) FIG. 12 is a perspective view showing a second side of the guide of FIG. 11;
- (14) FIG. 13 is a perspective view of an alternative guide unit suitable for use with the tray arrangement of FIG. 2, the guide unit including two guides coupled together as a unit;
- (15) FIG. 14 is a front perspective of a portion of the tray arrangement of FIG. 9;
- (16) FIG. 15 is a front elevational view of the tray arrangement of FIG. 9;
- (17) FIG. 16 is an enlarged view of a portion of FIG. 15;
- (18) FIG. 17 is a front, first side perspective view of a first example cassette suitable for use with the tray arrangement of FIG. 2, the first cassette carrying two groups of LC ports separated by an intermediate region at a front end of the first cassette;
- (19) FIG. 18 is a front, second side perspective view of the first cassette of FIG. 17, the second side being opposite the first side;
- (20) FIG. 19 is a front elevational view of the first cassette of FIG. 17 with the front and rear port members removed;
- (21) FIG. 20 is a rear elevational view of the first cassette of FIG. 19;
- (22) FIG. 21 is a front perspective view of the first cassette of FIG. 17 carrying two groups of MPO ports separated by the intermediate region at the front end of the first cassette;
- (23) FIG. 22 is a front perspective view of the first cassette of FIG. 17 carrying two groups of SN ports separated by the intermediate region at the front end of the first cassette;
- (24) FIG. 23 is a perspective view of the first cassette of FIG. 17 with the front and rear port members exploded outwardly from the cassette body to show the front and rear apertures and a release handle exploded outwardly from a cassette body to show a stop member carried by the cassette body;
- (25) FIG. 24 is a side elevational view of the stop member and a portion of the cassette body of FIG. 23;
- (26) FIG. 25 is a front elevational view of the cassette body of the first cassette of FIG. 17;
- (27) FIG. 26 is a perspective view of the release handle of FIG. 23 showing an externally-facing side of the release handle, the release handle defining a camming groove having first and second ramped surfaces;
- (28) FIG. 27 is an enlarged view of the camming groove of the release handle and stop surfaces of the cassette body of FIG. 26;
- (29) FIG. 28 is an enlarged view of the forward grip portion of the release handle;

(30) FIG. 29 is a side elevational view of the cassette of FIG. 17 shown with the release handle in a neutral position relative to the cassette body;

(31) FIG. 29A is an enlarged view of a portion of FIG. 29 showing a camming member disposed along the camming groove of the release handle;

(32) FIG. 30 is a side elevational view of the cassette of FIG. 17 shown with the release handle in a forwardly-extended position relative to the cassette body;

(33) FIG. 30A is an enlarged view of a portion of FIG. 30 showing the camming member disposed along the camming groove of the release handle;

(34) FIG. 31 is a side elevational view of the cassette of FIG. 17 shown with the release handle in a rearwardly-extended position relative to the cassette body;

(35) FIG. 31A is an enlarged view of a portion of FIG. 31 showing the camming member disposed along the camming groove of the release handle;

(36) FIG. 32 is front perspective view of the first cassette of FIG. 17 having an alternative latching arrangement and alternative cover, the cover being raised relative to the cassette body sufficient to expose the alternative stop members;

(37) FIG. 33 is a perspective view of an alternative release handle for use with the alternative latching arrangement of FIG. 32;

(38) FIG. 34 is an enlarged view of the alternative latching arrangement of FIG. 32 showing the stop members resting on the camming member of the release handle when the release handle is disposed in the neutral position;

(39) FIG. 35 is a front, first side perspective view of a second example cassette suitable for use with the tray arrangement of FIG. 2, the second cassette carrying three groups of front ports separated by intermediate regions at a front end of the second cassette;

(40) FIG. 36 is a front, second side perspective view of the second cassette of FIG. 35, the second side being opposite the first side;

(41) FIG. 37 is a front elevational view of the second cassette of FIG. 35;

(42) FIG. 38 is a rear elevational view of the second cassette of FIG. 36;

(43) FIG. 39 is a front, first side perspective view of a third example cassette suitable for use with the tray arrangement of FIG. 2, the third cassette carrying four groups of front ports separated by intermediate regions at a front end of the third cassette;

(44) FIG. 40 is a front, second side perspective view of the third cassette of FIG. 39, the second side being opposite the first side;

(45) FIG. 41 is a front elevational view of the third cassette of FIG. 39;

(46) FIG. 42 is a rear elevational view of the third cassette of FIG. 39;

(47) FIG. 43 is a front, first side perspective view of a fourth example cassette suitable for use with the tray arrangement of FIG. 2, the fourth cassette carrying six groups of front ports separated by intermediate regions at a front end of the fourth cassette;

(48) FIG. 44 is a front, second side perspective view of the fourth cassette of FIG. 43, the second side being opposite the first side;

(49) FIG. 45 is a front elevational view of the fourth cassette of FIG. 43;

(50) FIG. 46 is a rear elevational view of the fourth cassette of FIG. 43; and

(51) FIG. 47 is a perspective view of a fifth example cassette configured to connect a like number of front and rear plug connectors, the fifth cassette being shown with an open top;

(52) FIG. 48 is a rear elevational view of a portion of a tray arrangement including a cassette mounted to guides carried by the tray arrangement;

(53) FIG. 49 is a perspective view of a second example tray arrangement configured to be mounted within the chassis of FIG. 1, the tray arrangement including a tray carrying a plurality of guides;

(54) FIG. 50 is a top plan view of the tray arrangement of FIG. 49;

(55) FIG. 51 is a first perspective view of an example guide suitable for use with the tray arrangement of FIG. 49;

- (56) FIG. 52 is a second perspective view of the guide of FIG. 51;
- (57) FIG. 53 is a bottom plan view of the tray of FIG. 49 with a portion of the tray enlarged for ease in viewing;
- (58) FIG. 54 is a front elevational view of a portion of the main region of the tray arrangement of FIG. 49;
- (59) FIG. 55 shows the guides of FIG. 54 mounted to a thicker tray;
- (60) FIG. 56 is a perspective view of an example countersink disposed at the main region of the tray arrangement of FIG. 53;
- (61) FIG. 57 shows a portion of an example transition arrangement of an example release handle shown exploded from an example stop member of an example latching arrangement of any of the cassettes shown herein;
- (62) FIG. 58 is a front elevational view of a portion of a communications arrangement including first and second cassettes mounted to the tray arrangement of FIG. 2, the first and second cassettes having the port members removed for ease in viewing the front apertures to show the even spacing between the front apertures; and
- (63) FIG. 59 is a perspective view of a sixth example cassette configured to connect a like number of front and rear plug connectors, the sixth cassette being shown with an open top.

DETAILED DESCRIPTION

- (64) Reference will now be made in detail to exemplary aspects of the present disclosure that are illustrated in the accompanying drawings. Wherever possible, the same reference numbers will be used throughout the drawings to refer to the same or like parts.
- (65) The present disclosure is directed to a communications panel **100** configured to mount to a rack R. The communications panel **100** includes a chassis **105** holding one or more tray arrangements **110, 310** (e.g., see FIGS. 3-7). Each tray arrangement **110, 310** spans a width W of the chassis **105**. In some implementations, the tray arrangements **110, 310** are stationary within the chassis **105**. In other implementations, the tray arrangements **110, 310** are slidable along a depth D of the chassis **105** between two or more positions. Each tray arrangement **110, 310** is configured to support one or more cassettes **200** carrying ports (e.g., optical ports, electrical ports, hybrid ports, etc.) configured to receive plug connectors. A tray arrangement **110, 310** populated with one or more cassettes **200** is referred to herein as a communications arrangement **108**.
- (66) As will be discussed in more detail herein, a cassette **200** carries one or more front ports at a front of the cassette **200**. The front ports are configured to receive plug connectors. In some implementations, the front ports are optical ports configured to receive optical plug connectors. In other implementations, the front ports may be electrical ports configured to receive electrical plug connectors, hybrid ports configured to receive hybrid plug connectors, or a mixture thereof. In some implementations, a cassette **200** carries single-fiber front ports (e.g., LC front ports). In other implementations, a cassette **200** carries multi-fiber front ports (e.g., MPO front ports, SN front ports offered by Senko, etc.). In still other implementations, the same cassette **200** may carry a mix of two or more types of front ports (e.g., a mixture of MPO and LC ports).
- (67) In some implementations, the cassette **200** carries one or more rear ports (e.g., optical port, electrical port, hybrid port, etc.) at the rear of the cassette **200**. Each rear port is configured to receive a plug connector. Intermediate optical fibers within the cassette connect the front and rear ports. In other implementations, the cassette **200** carries ports only at the front of the cassette **200**. In such implementations, a rear of the cassette **200** is configured to enable optical fibers or one or more optical fiber cables to extend into/onto the cassette **200** and be routed towards the front ports.
- (68) The cassettes **200** are slidably mounted to the tray arrangement **110, 310** along guides **150, 350**. As shown in FIG. 2, the tray arrangement **110, 310** includes a main region **112, 312** that extends along a forward-rearward axis FR between a front end **114, 314** and a rear end **116, 316** of the main region **112, 312**. The main region **112, 312** also extends along a lateral axis LA between opposite first and second ends **118, 120, 318, 320** of the main region **112, 312**. The main region

112, 312 of the tray arrangement **110, 310** carries the guides **150, 350**. Each guide **150, 350** extends parallel to the forward-rearward axis FR. The guides **150, 350** are spaced from each other along the lateral axis LA.

(69) The guides **150, 350** are configured to slidably receive a plurality of cassettes **200** along the guides **150, 350** from either the front end **114, 314** of the main region **112, 312** or from the rear end **116, 316** of the main region **112, 312** at a discretion of a user. Interaction between the guides **150, 350** and the cassettes **200** will be discussed in more detail herein.

(70) The guides **150, 350** and the cassettes **200** are configured so the sizes of the cassettes **200** need not be in integer increments of each other to each fit on the same tray arrangement **110, 310** with the same configuration of guides **150, 350**. For example, the tray arrangement **110, 310** may receive a first cassette **200** having a first width and a second cassette having a second width that is 1.5 times the first width. Accordingly, the same tray can be fully populated by a plurality of cassettes having the first width or by a plurality of cassettes having the second width at the discretion of the user without modifying the guides or the tray. In other cases, trays of different widths can be mixed on the tray.

(71) In FIG. 3, the tray arrangement **110** of FIG. 2 is shown fully populated by first cassettes **200A** having the first width to form a first example communications arrangement **108**. FIG. 4 shows the tray arrangement **110** of FIG. 2 fully populated by second cassettes **200B** having a second width that is larger than the first width to form a second example communications arrangement **108**. The configuration (e.g., positioning or spacing) of the guides **150** has not been modified between the two images. In the example shown, the second width is about 1.5 times the first width. FIG. 5 shows the tray arrangement **110** of FIG. 2 populated by a combination of the first and second cassettes **200A, 200B**. FIG. 6 shows the tray arrangement **110** of FIG. 2 fully populated by third cassettes **200C** having a third width that is larger than the second width (e.g., approximately twice the width of the first width). FIG. 7 shows the tray arrangement **110** of FIG. 2 fully populated by fourth cassettes **200D** having a fourth width that is larger than the third width (e.g., approximately three times the width of the first width). The positioning of the guides **150** remains constant in all five of these iterations. These same cassette configurations can be mounted to the tray arrangement **350** of FIGS. 49-51 as well.

(72) In various implementations, a cassette **200** (e.g., any of cassettes **200A, 200B, 200C, 200D**) can be a base-8 cassette, a base-12 cassette, or another type of cassette (e.g., a base-2 cassette, a base-16 cassette, a base-24 cassette, etc.). A base-8 cassette receives fibers at the rear (e.g., through a rear adapter or through fibers extending into the cassette) in increments of eight whereas a base-12 cassette receives fiber at the rear in increments of twelve. In certain examples, a base-16 cassette receives fibers at the rear in increments of sixteen and a base-24 cassette receives fibers at the rear in increments of twenty-four. In certain implementations, a base-8 cassette receives plug connectors having eight live fibers at a rear of the cassette **200**, a base-12 cassette receives plug connectors having twelve live fibers at a rear of the cassette **200**, a base-16 cassette receives plug connectors having sixteen live fibers at a rear of the cassette **200**, and a base-24 cassette receives plug connectors having twenty-four live fibers at a rear of the cassette **200**.

(73) In certain implementations, a base-12 cassette has a larger width than a base-8 cassette. For example, a base-12 cassette providing a row of six duplex-LC front ports (i.e., twelve LC front ports) may be wider than a base-8 cassette providing a row of four duplex-LC front ports (i.e., eight LC front ports). In an example, such a base-12 cassette may be 1.5 times as wide as the base-8 cassette. In such implementations, the tray arrangement **110** of FIG. 2 could be populated with the base-8 cassettes, the base-12 cassettes, or a combination thereof without modification to the arrangement of the guides **150**. In other implementations, however, a base-8 cassette and a base-12 cassette can have the same width depending on port type.

(74) FIG. 8 shows the example tray arrangement **110** of FIG. 2 including a tray **122** onto which various components (e.g., guides **150**) are mounted to form the tray arrangement **110**. In certain

implementations, the tray **122** extends along the lateral axis LA between the first and second ends **118**, **120** of the tray arrangement **110**. In certain implementations, the guides **150** are mounted to the tray **122**.

(75) In the example shown, the tray **122** includes a front portion **124**, a rear portion **126**, and an intermediate portion **128**. The front portion **124** is disposed toward the front end **114** of the tray arrangement **110** and the rear portion **126** is disposed toward the rear end **116** of the tray arrangement **110**. The intermediate portion **128** is disposed between the front portion **124** and the rear portion **126** along the forward-rearward axis FR. The intermediate portion **128** is raised along a height H of the tray arrangement **110** relative to the front portion **124** (e.g., see FIG. **10**).

(76) The guides **150** are mounted to the tray arrangement **110** so that each guide **150** extends across the intermediate portion **128** along the forward-rearward axis FR. In certain implementations, the guides **150** are mounted to the front portion **124** of the tray **122** and to the rearward portion **126** of the tray **122**. In certain examples, each guide **150** also extends across the forward and rearward portions **124**, **126** along the forward-rearward axis FR.

(77) In certain implementations, the tray arrangement **110** includes a front extension arrangement **130** that mounts to the front portion **124** of the tray **122** (e.g., see FIGS. **2** and **8**). In some examples, the front extension arrangement **130** forms part of the main region **112** of the tray arrangement **110** and defines the front end **114** of the main region **112**. In other examples, the front portion **124** of the tray **122** defines the front end **114** of the main region **112**. In certain implementations, the front extension arrangement **130** extends between the first and second ends **118**, **120** of the tray arrangement **110**. In certain implementations, the front extension arrangement **130** is disposed no higher than the intermediate portion **128** of the tray **122**. In certain examples, the front extension arrangement **130** is disposed lower than the intermediate portion **128** of the tray **122**.

(78) In certain implementations, the tray arrangement **110** includes a rear extension arrangement **132** that mounts to the rearward portion **126** of the tray **122**. In some examples, the rear extension arrangement **132** forms part of the main region **112** of the tray arrangement **110** and defines the rear end **116** of the main region **112**. In other examples, the rearward portion **126** of the tray **122** defines the rearward end **116** of the main region **112**. In certain implementations, the rear extension arrangement **132** extends between the first and second ends **118**, **120** of the tray arrangement **110**. In certain implementations, the rear extension arrangement **132** is disposed no higher than the intermediate portion **128** of the tray **122**. In certain examples, the rear extension arrangement **132** is disposed lower than the intermediate portion **128** of the tray **122**.

(79) In certain implementations, the front extension arrangement **130** and/or the rear extension arrangement **132** are formed of a different material than the tray **122**. For example, the tray **122** may be formed of metal while the front and/or rear extension arrangements **130**, **132** are formed of plastic or other materials. In certain implementations, the front extension arrangement **130** and/or the rear extension arrangement **132** defines notches in which portions of the guides **150** extend.

(80) In certain implementations, the tray arrangement **110** includes a cable support arrangement **135** extending forwardly of the main region **112** of the tray arrangement **110**. The cable support arrangement **135** includes a cable support bar **134** that extends parallel to the lateral axis LA of the tray arrangement **110** to support cables routed to the front ports of the cassettes **200** mounted to the tray arrangement **110**. The cable support bar **134** is coupled to the main region **112** of the tray arrangement **110** by arms **136**, **138**. In certain examples, the arms **136**, **138** space the support bar **134** away from the front end **114** of the tray main region **112** sufficient to provide finger access to plug connectors received at the front ports of the cassettes **200**. In some examples, the support bar **134**, first arm **136**, and second arm **138** are monolithically formed with the tray **122**. In other examples, the cable support arrangement **135** is a separate piece coupled to the main region **112** of the tray arrangement **110** using fasteners, latches, or other attachment mechanisms.

(81) FIGS. **11** and **12** illustrate an example guide **150** suitable for use with the tray arrangement **110**

of FIG. 2. The guide **150** extends along a length GL (FIG. 9) between a front end **152** and a rear end **154** and along a height H (FIG. 10) between a bottom and a top surface **164**. The guide **150** also has opposite first and second sides **156**, **158** facing orthogonally to length GL and the height H.

(82) The guide **150** is configured to engage (e.g., interconnect) with a cassette from only the second side **158**. For example, the second side **158** defines cassette engagement structure and the first side **156** does not. In the example shown, the first side **156** defines a closed surface **160** and the second side **158** defines a groove **162** that extends along the length GL between opposite open ends. In some examples, the guide **150** has an L-shaped cross-sectional profile (e.g., see FIG. 15). In other examples, the guide **150** has a C-shaped cross-sectional profile along at least part of the length GL of the guide **150** (e.g., see FIG. 13).

(83) The guides **150** each define a top surface **164** extending along the length GL of the guide **150**. In certain examples, the top surface **164** of a guide **150** defines a ramped surface **172** at the first and second open ends of the groove **162**. The top surface **164** defines a notch **166** at an intermediate position between the first and second open ends of the groove **162**. In certain examples, the notch provides access to the groove **162** through the top surface **164**. In certain implementations, the notch **166** provides access to a forward-facing catch surface **168** and a rearward-facing catch surface **170** at opposite ends of the notch **166**.

(84) In certain implementations, the guides **150** are configured to be mounted to the main region **112** of the tray arrangement **110** (e.g., to the tray **122**). In some examples, the guides **150** include pegs **174** that can be inserted into apertures defined through the main region **112** to attach the guides **150** to the tray arrangement **110**. In various examples, the pegs **174** can be attached to the main region **112** by heating, ultrasonically welding, adhesive, friction, or another mechanism. In other examples, the guides **150** can be fastened, soldered, latched, or otherwise attached to the tray.

(85) In certain implementations, a guide **150** includes side tabs **176** extending outwardly from the first and second sides **156**, **158** of the guide **150**. The side tabs **176** may carry pegs **174** or other attachment structure. In certain examples, the side tabs **176** provide stability to the guides **150**. In certain examples, an example guide **150** includes a first pair of side tabs **176** at the front end **152** and a second pair of side tabs **176** at the rear end **154**. In the example shown in FIG. 9, the first pair of side tabs **176** are mounted to the front end portion **124** of the tray **122** and the second pair of side tabs **176** are mounted to the rear end portion **126** of the tray **122**. In certain examples, an example guide **150** includes a third pair of side tabs **176** extending outwardly from an intermediate position along the length GL of the guide **150**. In an example, the third pair of side tabs **176** align with the notch **166**.

(86) FIG. 13 shows an alternative guide unit **178** including a plurality of guides **150** connected together with webbing **180**. In the example shown, the webbing **180** connects two guides. In other examples, the webbing **180** can connect three, four, six, twelve, or any desired number of guides **150**. The guide unit **178** enables multiple guides **150** to be mounted to the main region **112** of the tray arrangement **110** simultaneously. In certain implementations, the guide unit **178** also may include pegs **174** for heat staking, ultrasonically welding, or otherwise securing the guide unit **178** to the tray arrangement **110**. In certain implementations, the guide unit **178** also may include side tabs **176**.

(87) The guides **150**, **350** extend across the main region **112**, **312** of the tray arrangement **110**, **310** along the lateral axis LA. In certain implementations, the guides **150**, **350** are spaced a common distance CD apart from each other along the lateral axis LA (e.g., see FIGS. 14-16). A bay **140**, **340** is a space extending outwardly from the second side **158**, **358** of a guide **150**, **350** by the common distance CD. In most cases, the bay **140**, **340** extends to the first side **156**, **356** of an adjacent guide **150**, **350**. In certain cases, a bay **140**, **340** is bordered by only one guide **150**, **350** (e.g., see the left-most bay **140**, **340** of FIGS. 15 and 50). In such a case, the bay **140**, **340** extends towards a sidewall of the chassis **105**.

(88) FIGS. 49-51 illustrate another example implementation of a tray arrangement 310 suitable for use in receiving any of the cassettes 200 disclosed herein. FIG. 49 shows the example tray arrangement 310 including a planar tray 322 onto which various components (e.g., guides 350) are mounted to form the tray arrangement 310. In certain implementations, the tray 322 extends along the lateral axis LA between the first and second ends 318, 320 of the tray arrangement 310. In the example shown, the tray 322 defines the main region 312 of the tray arrangement 310 at which the guides 350 mount.

(89) In certain implementations, the tray 322 defines a front cable management region 324 and a rear cable management region 326. In certain examples, the front cable management region 324 and rear cable management region 326 are monolithically formed with the tray 322. In certain implementations, the front cable management region 324 includes a cable support arrangement 335. The cable support arrangement 335 includes a cable support bar 334 that extends parallel to the lateral axis LA of the tray arrangement 310 to support cables routed to the front ports of the cassettes 200 mounted to the tray arrangement 310. In certain implementations, the rear cable management region 326 defines a cable support surface for cables routed to the rear ends 206 of the cassettes 200.

(90) One or more front finger access apertures 328 are defined between the main region 312 and the front cable management region 324. One or more rear finger access apertures 330 are defined between the main region 312 and the rear cable management region 326. In some examples, the tray 322 defines a different number of front finger access apertures 328 than rear finger access apertures 330. The finger access apertures 328, 330 provide finger access to the front and/or rear ports carried by any cassettes 200 mounted to the tray arrangement 310.

(91) FIGS. 51 and 52 illustrate another example guide 350 suitable for use with the tray arrangement 310. The guide 350 extends along a length between a front end 352 and a rear end 354 and along a height between a bottom and a top surface 364. The guide 350 also has opposite first and second sides 356, 358 facing orthogonally to length and the height. In certain implementations, the guide 350 is substantially similar to the guide 150 of FIGS. 11 and 12, except that the guide 350 does not include side tabs 176.

(92) The guide 350 is configured to engage (e.g., interconnect) with a cassette from only the second side 358. For example, the second side 358 defines cassette engagement structure and the first side 356 does not. In the example shown, the first side 356 defines a closed surface 360 and the second side 358 defines a groove 362 that extends along the length between opposite open ends. In some examples, the guide 350 has an L-shaped cross-sectional profile (e.g., see FIG. 54).

(93) The guides 350 each define a top surface 364 extending along the length of the guide 350. In certain examples, the top surface 364 of a guide 350 defines a ramped surface 372 at the first and second open ends of the groove 362. The top surface 364 defines a notch 366 at an intermediate position between the first and second open ends of the groove 362. In certain examples, the notch 366 provides access to the groove 362 through the top surface 364. In certain implementations, the notch 366 provides access to a forward-facing catch surface 368 and a rearward-facing catch surface 370 at opposite ends of the notch 366.

(94) In certain implementations, the guides 350 are configured to be mounted to the main region 312 of the tray arrangement 310 (e.g., to the tray 322). In some examples, the guides 350 are individually mounted to the tray 322. In other examples, the guides 350 are mounted to the tray 322 in one or more units with each unit including two or more guides 350.

(95) In some examples, the guides 350 include pegs 374 that can be inserted into apertures 355 defined through the main region 312 and heated to attach the guides 350 to the tray arrangement 310. In other examples, the guides 350 can be attached to the main region 312 by fasteners, latches, friction-fit pegs, welding, soldering, or other attachment mechanisms.

(96) As shown in FIG. 50, the guides 350 are mounted to the main region 312 of the tray 322 so that each guide 350 terminates before reaching the finger access apertures 328, 330. As shown in

FIG. 53, the apertures 355 may lead to countersinks or pockets 357 at the bottom of the tray 322. For example, the countersinks 357 may be sized to receive material melted or otherwise liquefied from the pegs of the guides 350. In an example, the countersinks 357 are sized so that the flowable material is flush with the bottom of the tray 322 when the guides 350 are attached to the tray 322. (97) In certain implementations, the main region 312 defines rows of apertures 355 through which the guides 350 can be staked, fastened, or otherwise coupled to the tray 322. In some implementations, the apertures 355 of each row are aligned along respective axes A1. In other implementations, one or more of the apertures 355 in a row may be laterally offset from each other. For example, as shown in FIG. 53, front and rear apertures 355A, 355F of each row may be aligned along the axis A1 while intermediate apertures 355B-355E are offset along the lateral axis A relative to the axis A1. In the example shown, apertures 355C and 355E are offset to be tangent to a second axis A2 spaced in a first direction from the first axis A1 and apertures 355B and 355D are offset to be tangent to a third axis A3 spaced in an opposite second direction from the first axis A1. Offsetting the apertures 355 in a row may increase the stability of the guide 350. In certain implementations, the apertures 355 may be positioned in a configuration to add a poke-yoke to inhibit installing the guides 350 backwards. For example, the guide 358 shown in FIG. 53 may be modified to have an odd number of pegs.

(98) As shown in FIGS. 54 and 55, a thickness of the tray arrangement 310 may vary. For example, FIG. 54 illustrates two example guides 350 mounted to a first tray 322A having a first thickness T1 and the same two guides 350 mounted to a second tray 322B having a second thickness T2. In other examples, additional components can be mounted to the tray 322A to create a thickness of T2.

(99) In some implementations, different guides 350 with different sizes of pegs 374 are used with each tray 322A, 322B. For example, the guide 350 used with the thicker tray 322B may have a longer peg 374. In other implementations, the same guides 350 can be utilized with trays 322A, 322B of different thicknesses T1, T2. For example, each of the trays 322A, 322B may have a respective countersink 357 sized based on the length of the peg 374 extend through the aperture 355. In still other examples, the same countersink 357 may be used with both trays 322A, 322B.

(100) In some such examples, the, each tray 322A, 322B may have a common countersink 357 that is configured to accommodate different amounts of peg material. For example, FIG. 56 illustrates a countersink 357 sized to receive the flowable material from a peg 374 extending through the thicker tray 322B so that the flowable material is about flush with the bottom of the tray 322B. The countersink 357 of FIG. 56 defines channels or wells 359 to accommodate additional flowable material when the peg 374 is utilized with the thinner tray 322A. It will be understood that a greater or lesser number of channels or wells 359 can be provided at the countersink 357 and in other configurations.

(101) In other such examples, the countersink 357 may be sized so that the flowable material is flush with a bottom of the tray 322A for the thinner tray 322A, but fills only a portion of the countersink 357 for the thicker tray 322B. In certain implementations, a tool that melts or otherwise liquefies the pegs 374 may include a protrusion that extends partially into the countersink 357 to press or displace the flowable material towards the periphery of the countersink 357 for better adhesion.

(102) Referring now to FIGS. 17-20, the cassettes 200 (e.g., cassettes 200A, 200B, 200C, and 200D) are configured to slidably mount to the tray arrangement 110 using the guides 150, 350. A cassette 200 includes a cassette body 202 that extends along a width W2 between opposite first and second ends 208, 210, along a length L2 between front and rear ends 204, 206, and along a height H2 (FIG. 19) between a bottom and a top. The length L2, width W2, and height H2 are orthogonal to each other. The cassette 200 includes a bottom rail 220 (FIG. 19) that is configured to fit (i.e., inter-connect) within the groove 162, 362 of a respective one of the guides 150, 350. The bottom rail 220 is configured to slide along the groove 162, 362 from either the open front end or the open

rear end of the groove **162, 362**.

(103) In certain implementations, the cassette body **202** includes an end rail **218** (FIGS. **19** and **23**) at the first end **208** of the cassette body **202**. The end rail **218** is configured to fit within the groove **162, 362** of a respective one of the guides **150, 350**. The end rail **218** is configured to slide along the groove **162, 362** from either the open front end or the open rear end of the groove **162, 362**. In the example shown in FIGS. **19** and **20**, the bottom rail **220** and the end rail **218** would slide along adjacent guides **150, 350**. In other examples, however, the bottom rail **220** and the end rail **218** are configured to slide along non-adjacent guides **150, 350** (e.g., see FIG. **37**). In certain examples, each guide **150, 350** is configured to inter-connect with no more than one cassette **200**.

(104) In certain examples, the end rail **218** and the bottom rail **220** of each cassette body **202** extend in a common direction from a base end **218a, 220a** attached to the cassette body **202** to a free end **218b, 220b**. In an example, the common direction extends along the width **W2** of the cassette body **202**. In some examples, the free ends **218b, 220b** of the rails **218, 220** extend parallel with the height **H2** of the cassette body **202**. In other examples, the free ends **218b, 220b** of the rails **218, 220** are angled relative to the height **H2** of the cassette body **202** (e.g., see FIGS. **19** and **20**).

(105) The second end **210** of the cassette body **202** is not configured to engage a guide **150, 350**. In certain examples, the cassette body **202** is devoid of rails (i.e., does not include any rails) at the second end **210** (e.g., see FIG. **18**). Rather, the second end **210** of the cassette body **202** directly opposes the first side **156, 356** (e.g., the closed surface **160, 360**) of the guide **150, 350**. In certain examples, the second end **210** of the cassette body **202** defines a generally flat surface. In certain examples, the second end **210** of the cassette body **202** is spaced from the first side **156, 356** of the guide **150, 350** sufficient to avoid contacting the guide **150, 350**.

(106) The cassette body **202** defines a two or more front apertures (e.g., three front apertures, four front apertures, six front apertures, etc.) **212** at the front end **204**. Each of the front apertures **212** is configured to hold one or more optical adapters **230, 232, 234, 236**. In certain implementations, the front apertures **212** are separated from each other by respective intermediate regions **214**. For example, in FIG. **19**, the cassette body **202** defines a first front aperture **212A** separated from a second front aperture **212B** by an intermediate region **214**.

(107) As shown in FIG. **58**, the intermediate regions **214** of a cassette **200** have a consistent size so that adjacent front apertures **212** of a cassette **200** are spaced from each other by a gap **G1** that extends along the width **W2** of the cassette **200**. In certain examples, the front apertures **212** of a cassette **200** also have a consistent size extending along the width **W2** of the cassette **200**. In certain examples, all cassettes **200** that fit on the tray arrangement **110** have equally sized front apertures **212**. In certain examples, the cassettes **200** are configured so that adjacent front apertures **212** of adjacent cassettes **200** (e.g., the right-most front aperture **212** of a first cassette **200** and the left-most front aperture **212** of a second cassette **200**) are spaced from each other by a spacing **G2** that is the same (within manufacturing tolerances) as the spacing **G1** of the adjacent front apertures **212** of the same cassette **200** (e.g., see FIG. **58**). Making the spacing between adjacent front apertures **212** of adjacent cassettes **200** consistent with the spacing between adjacent front apertures **212** of the same cassette **200** facilitates mixing different sizes of cassettes **200** on the tray arrangement **110** at a discretion of the user.

(108) As shown in FIGS. **19** and **20**, the cassette body **202** defines a bottom channel **222** extending along the length **L2** of the cassette body **202**. The bottom channels **222** are sized to receive guides **150, 350** to enable a cassette **200** to extend over one or more guides **150, 350**. In some implementations, the channels **222** are sized so that a top of the channel **222** is spaced from the top surface **164, 364** of the guide **150, 350** received therein. In other implementations, the channels **222** are sized so that a top of the channel **222** rests on and slides along the top **164, 364** of the guide **150, 350**. Each cassette **200** spans at least two bays **140, 340** of the tray arrangement **110, 310**. In certain examples, the bottom channel **222** is disposed at an intermediate region **214** of the cassette

200 between two front apertures **212**.

(109) In certain implementations, each intermediate region **214** defines a bottom channel **222**. Accordingly, a cassette **200** having two front apertures **212A**, **212B** defines a single bottom channel **222**. A cassette **200** having three front apertures **212** defines two bottom channels **222-a** first bottom channel **222** disposed between the first front aperture **212A** and the second front aperture **212B** and a second bottom channel **222** disposed between the second front aperture **212B** and a third front aperture **212** (e.g., see FIG. 37). A cassette **200** having four front apertures **212** defines three bottom channels **222** (e.g., see FIG. 41). A cassette **200** having six front apertures **212** defines five bottom channels **222** (e.g., see FIG. 45).

(110) In certain implementations, a punch-out cover may be initially provided at one or more of the front apertures **212** so a respective optical adapter is mounted at fewer than all of the front apertures **212**. In such cases, a user has the flexibility to select a position for a front optical adapter to facilitate cable routing.

(111) In certain implementations, the bottom rail **220** of the cassette body **202** is disposed within the bottom channel **222**. The bottom rail **220** extends less than a width of the bottom channel **222** to accommodate the guide **150**, **350** within the bottom channel **222** (e.g., see FIG. 48). In certain examples, the bottom rail **220** is flush with a bottom of the cassette body **202**. In certain examples, the bottom rail **220** and the end rail **218** are coplanar with each other.

(112) In the example shown in FIG. 48, a cassette **200B** is mounted to guides **150**, **350** of a tray arrangement **110**. The cassette **200B** spans three bays **140**, **340-a** first bay **140**, **340** disposed between the first guide **150A**, **350A** and the second guide **150B**, **350B**, a second bay **140**, **340** disposed between the second and third guides **150B**, **350B**, **150C**, **350C** and a third bay **140**, **340** disposed between the third guide **150C**, **350C** and a fourth guide **150D**, **350D**. The cassette **200B** defines bottom channels **222** that receive the second and third guides **150B**, **350B**, **150C**, **350C**. The first guide **150A**, **350A** inter-connects with the end rail **218** of the cassette **200B**. The second guide **150B**, **350B** does not inter-connect with any structure of the cassette **200B**, but rather slides within one of the bottom channels **222**. In an example, the cassette **200B** may slide along a top **164**, **364** of the second guide **150B**, **350B**. The third guide **150C**, **350C** inter-connects with the bottom rail **220** of the cassette **200B** within the other bottom channel **222**. In the example shown, the cassette **200B** extends towards, but does not engage a fourth guide **150D**, **350D** at an opposite side of the third bay **140**, **340**. Rather, the fourth guide **150D**, **350D** receives the end rail **218** of an adjacent cassette **200**. In other implementations, the tray arrangement **110**, **310** may not include a fourth guide **150D**, **350D**. Similarly, the first guide **150**, **350** does not engage the cassette **200** disposed at an opposite side of the first guide **150A**, **350A** from the cassette **200B**.

(113) In certain implementations, each front aperture **212** of a cassette **200** has a common size. In certain examples, each of the front apertures **212** has a footprint sized to two standardized ports. As the term is used herein, a standardized port refers to a sufficient spacing to accommodate an MPO port or a duplex-LC port at a discretion of the user. In FIG. 17, the cassette body **202** is shown carrying a quadruplex LC adapter **230** at each of the front apertures **212**. Each quadruplex LC adapter **230** defines two duplex-LC ports (i.e., four LC ports). In other examples, the cassette body **202** may carry a duplex MPO adapter **234** (e.g., see FIG. 21), two quadruplex SN adapters **236** (e.g., see FIG. 22), two SC adapters, or any desired adapter type that fits in a quadruplex LC adapter footprint. In still other implementations, the front apertures **212** may be sized to handle other port footprints.

(114) In certain examples, cassette **200** is configured to fit one front aperture **212** per bay **140**. In certain examples, each tray arrangement **110** defines at least twelve bays **140**. In certain examples, each front aperture **212** is configured to fit four LC ports. In such examples, each tray arrangement **110** is configured to hold forty-eight LC ports. In certain examples, each front aperture **212** is configured to hold four SN ports. In such examples, each tray arrangement **110** is configured to hold forty-eight SN ports (or ninety-six fibers). In certain examples, each front aperture **212** is

configured to hold a duplex MPO ports—each receiving eight, twelve, sixteen, or twenty-four live fibers. In such examples, each tray arrangement **110** is configured to hold twenty-four MPO ports. (115) In certain implementations, three tray arrangements **110** fit within a 1 RU chassis. In certain examples, each 1 RU chassis may hold at least 144 LC ports. In certain examples, each 1 RU chassis may hold at least 144 SN ports (or 288 fiber connections). In certain examples, each 1 RU chassis may hold at least 72 MPO ports (for 576 fiber connections, 864 fiber connections, 1,152 fiber connections, and 1,728 fiber connections depending on the number of live fibers received). (116) In certain implementations, the cassettes **200** are configured to lock to the guides **150**, **350** in at least one discrete position. Each cassette **200** includes a latching arrangement **240** that rides over the top **164**, **364** of a respective one of the guides **150**, **350**. The latching arrangement **240** includes a stop member **242** that drops into the notch **166**, **366** of the respective guide **150**, **350** to lock the cassette **200** to the guide **150**, **350**. The latching arrangement **240** also includes a release handle **244** to raise the stop member **242** out of the notch **166**, **366**.

(117) The stop member **242** is carried by the cassette body **202** at the first end **208**. The stop member **242** is movable relative to the cassette body **202** along a movement axis SM that extends parallel to the height H2 of the cassette **200**. In certain implementations, the stop member **242** is movable along the movement axis SM between a lock position and a release position. In certain examples, the stop member **242** is biased to the lock position.

(118) In certain implementations, the stop member **242** rides over the ramped surface **172**, **372** at the front end **152**, **352** or rear end **154**, **354** of the guide **150**, **350** when the cassette **200** is first mounted to the guides **150**, **350**. The ramped surfaces **172**, **372** transition the stop member **242** from the lock position to the release position. The top **164**, **364** of the guide **150**, **350** maintains the stop member **242** in the release position until the stop member **242** vertically aligns with the notch **166**, **366**. The notch **166**, **366** allows the stop member **242** to transition to the lock position.

(119) The release handle **244** is configured to move relative to the cassette body **202** along an actuation axis A between a neutral position (FIG. 29) and a forward extended position (FIG. 30). When in the neutral position, the release handle **244** enables the stop member **242** to be in the lock position. When disposed in the forward extended position, the release handle **244** transitions the stop member **242** to the release position. In certain implementations, the release handle **244** also can be moved relative to the cassette body **202** along the actuation axis A to a rearward extended position (FIG. 31). When disposed in the rearward extended position, the release handle **244** transitions the stop member **242** to the release position.

(120) When in the lock position, engagement surfaces **246**, **248** of the stop member **242** extend at least partially through a recess or gap **218e** in the end rail **218**. The first engagement surface **246** is configured to oppose the first catch surface **168**, **368** within the notch **166**, **366** of the guide **150**, **350** and the second engagement surface **248** is configured to oppose the second catch surface **170**, **370** when the stop member **242** is engaged with the notch **166**, **366**. Abutment between the first engagement surface **246** and the first catch surface **168**, **368** inhibits forward movement of the cassette **200** along the guides **150**, **350**. Abutment between the second engagement surface **248** and the second catch surface **170**, **370** inhibits rearward movement of the cassette **200** along the guides **150**, **350**. When in the release position, the engagement surfaces **246**, **248** of the stop member **242** are raised out of the notch **166**, **366** sufficient so that the engagement surfaces **246**, **248** do not abut the catch surfaces **168**, **368**, **170**, **370** upon movement of the cassette **200** relative to the guides **150**, **350**.

(121) In certain examples, the end rail **218** includes a front end rail **218c** and a rear end rail **218d** aligned along the length L2 of the cassette **200** (e.g., FIG. 24). The rear end rail **218d** is spaced from the front end rail **218c** along the length L2 of the cassette **200** to provide the gap **218e**. In other implementations, a recess can be provided in a continuous end rail **218**. When in the lock position, the stop member **242** extends at least partially into the recess or gap **218e** (e.g., see FIG. 24). When in the release position, the engagement surfaces **246**, **248** of the stop member **242** are

raised out of the recess or gap **218e**.

(122) In certain implementations, the stop member **242** is coupled to the cassette body **202** using one or more spring members **250**. In the example shown, first and second spring members **250** extend from opposite sides of the stop member **242**. In certain examples, the spring members **250** limit the movement of the stop member **242** to the movement axis SM. The spring members **250** bias the stop member **242** to the lock position.

(123) The release handle **244** is actuated by moving the release handle **244** in a different direction than the stop member **242** moves. In certain examples, the release handle **244** is moved orthogonally to the movement of the stop member **242**. In an example, the release handle **244** is moved along the forward-rearward axis FR of the tray arrangement **110** while the stop member **242** moves along the height H2 of the cassette **200**.

(124) In certain implementations, the stop member **242** is carried outside a main interior of the cassette body **202**. Accordingly, movement of the stop member **242** does not affect the optical fibers or other connections disposed within the main interior of the cassette body **202**. In certain examples, the cassette body **202** includes a base **260** and a cover **262** that cooperate to define the main interior. In certain examples, the stop member **242** is carried at an exterior of the base **260**, but is at least partially covered by the cover **262**. For example, the cover **262** may include an overhang portion **264** that extends over the stop member **242** (e.g., see FIGS. **20** and **25**). In some implementations, the cover **262** may include one or more latching members **266** to secure the cover **262** to the base **260**. In other implementations, the cover **262** may be secured to the base **260** by fasteners, welding, or other securement mechanisms.

(125) In certain implementations, the stop member **242** includes a camming member **252** that engages the release handle **244**. Interaction between the camming member **252** and the release handle **244** transitions the stop member **242** between the lock and release positions as will be described in more detail herein. In certain examples, the camming member **252** is disposed at an opposite end of the stop member **242** from the engagement surfaces **246**, **248**. For example, the camming member **252** may be disposed at a top of the stop member **242** while the engagement surfaces **246**, **248** are disposed at a bottom of the stop member **242**. In certain examples, the camming member **252** extends outwardly from the stop member **242** along the width W2 of the cassette **200**. In an example, the camming member **252** extends from the stop member **242** away from the cassette body **202** (e.g., see FIG. **23**). In another example, the camming member **252** extends from the stop member **242** towards the cassette body **202**.

(126) In certain implementations, the base **260** defines a channel **268** along the exterior of the cassette **200** at the first end **208**. The channel **268** is sized to hold the release handle **244**. The channel **268** extends along the length L2 of the cassette **200** past the stop member **242**. At least a portion of the stop member **242** is disposed within the channel **268**. In certain implementations, the overhang portion **264** of the cover **262** extends over the release handle **244**.

(127) As shown in FIGS. **26**, **27**, and **57**, the release handle **244** includes a transition arrangement **270** and a forward grip portion **276**. As best seen in FIG. **28A**, the transition arrangement **270** includes a ramped surface **272** along which the camming member **252** rides as the release handle **244** is moved along the actuation axis A between the neutral position and the forwardly extended position (e.g., see FIGS. **29** and **30**). As the camming member **252** rides along the ramped surface **272**, the stop member **242** moves with the camming member **252** along the movement axis SM (compare FIGS. **29** and **30**).

(128) In certain implementations, the ramped surface **272** is a first ramped surface and the transition arrangement **270** also includes a second ramped surface **274** extending in an opposite direction from the first ramped surface **272**. As the camming member **252** rides along the second ramped surface **274**, the stop member **242** moves with the camming member **252** along the movement axis SM. The camming member **252** rides along the second ramped surface **274** when the release handle **244** moves along the actuation axis A in a rearward direction relative to the

cassette body **202** to the rearward extended position (FIG. **31**).

(129) In certain implementations, the transition arrangement **270** straddles the stop member **242**. For example, the transition arrangement **270** may define a first pair of inner and outer ramped surfaces **272A**, **272B** disposed on opposite sides of the stop member **242** from each other and a second pair of ramped surfaces **274A**, **274B** disposed on opposite sides of the stop member **242** from each other. The stop member **242** may include a first camming member **252A** extending towards the cassette body **202** and a second camming member **252B** extending outwardly away from the cassette body **202**. The first camming member **252A** is configured to ride along the inner first and second ramped surfaces **272A**, **274A** and the second camming member **252B** is configured to ride along the outer first and second ramped surfaces **272B**, **274B**. By straddling the stop member **242**, the transition member **270** provides more stability to the movement of the stop member **242**.

(130) In other implementations, the stop member **242** may define a single camming member **252** and the transition arrangement **270** may define a single first ramped surface and a single second ramped surface along which the camming member **252** rides. In the example shown in FIG. **47**, the stop member **242** includes a single camming member extending towards the cassette body **202**. In the example shown in FIG. **47**, the first and second ramped surfaces define part of a triangular shaped aperture in the transition arrangement **270**.

(131) In certain implementations, the cassette body **202** and the release handle **244** are configured to limit movement of the release handle **244** relative to the cassette body **202** along the actuation axis **A** to between the forwardly extended position and the rearwardly extended position. For example, the cassette body **202** may define forward and rearward stop surfaces **254** that oppose forward and rearward abutment surfaces **256** on the release handle **244** (e.g., see FIG. **27**). When the release handle **244** is moved to the forwardly extended position, the forward abutment surface **256** engages or is close to engaging the forward stop surface **254** of the cassette body **202**. When the release handle **244** is moved to the rearwardly extended position, the rearward abutment surface **256** engages or is close to engaging the rearward stop surface **254** of the cassette body **202**.

(132) Accordingly, pulling the release handle **244** forwardly relative to the cassette body **202** releases the cassette **200** from the guide **150**, **350**. Continuing to pull forwardly on the release handle **244** causes the release handle **244** to entrain the cassette body **202** in the forward direction, thereby sliding the cassette body **202** along the guides **150**, **350** in the forward direction. Pushing the release handle **244** rearwardly relative to the cassette body **202** also releases the cassette **200** from the guide **150**, **350**. Continuing to push rearwardly on the release handle **244** causes the release handle **244** to entrain the cassette body **202** in the rearward direction, thereby sliding the cassette body **202** along the guides **150**, **350** in the rearward direction.

(133) In certain implementations, the first and second ramped surfaces **272**, **274** are defined by a cutout or aperture in the release handle **244**. In the example shown in FIG. **28A**, the first and second ramped surfaces **272**, **274** are defined by a V-shaped groove. In other examples, the first and second ramped surface **272**, **274** may be defined by a triangular aperture in the transition arrangement **270**. In still other examples, the cutout or aperture may have any desired shape including the ramped surface **272**, **274**.

(134) The release handle **244** extends forwardly of the cassette body **202** so that the forward grip portion **276** is disposed forwardly of the front end **204** of the cassette **200** (e.g., see FIGS. **17** and **18**). In certain implementations, the forward grip portion **276** is angled relative to a majority of the release handle **244** to facilitate grasping of the forward grip portion **276**. In certain examples, the forward grip portion **276** may be angled along the lateral axis **LA**. In an example, the forward grip portion **276** is angled away from the first end **118** of the tray arrangement **110** to facilitate grasping the grip portion **276** without interference from the chassis **105** of any components mounted at the first end **118** of the tray arrangement **110**.

(135) In certain implementations, the forward grip portion **276** is configured to flex or deflect

relative to a remainder of the release handle **244**. In certain examples, the forward grip portion **276** may include a grip member **280** attached to a remainder of the release handle **244** by a flexible section **282**. In certain examples, the flexible section **282** enables the grip member **280** to deflect along the width W2 of the cassette **200**. This deflection ability facilitates grasping of the grip member **280** when the cassettes **200** are densely packed on the tray arrangement **110**, especially when cables are routed to the front ports. In some examples, the flexible section **282** enables deflection of the grip member **280** along the height H2 of the cassette **200**. In certain examples, the flexible section **282** enables a reduced amount of deflection along the height H2 compared to along the width W2. In other examples, the flexible section **282** inhibits deflection of the grip member **280** along the height H2 of the cassette **200**.

(136) In certain implementations, the handle **244** also includes a rearward grip portion **278**. The release handle **244** extends rearwardly of the cassette body **202** so that the rearward grip portion **276** is disposed rearwardly of the rear end **206** of the cassette **200** (e.g., see FIGS. **17** and **18**). In certain examples, the rearward grip portion **278** has a different shape than the forward grip portion **276**. In certain examples, the rearward grip portion **278** is hook shaped. In certain examples, the rearward grip portion **278** is not deflectable relative to the transition arrangement **270**.

(137) FIGS. **32-34** illustrate an alternative latching arrangement **240'** suitable for use in locking the cassette **200** to a guide **150, 350**. The latching arrangement **240'** includes first stop member **242'** and second stop members **242'** extending along the channel **268** at the first end **208** of the cassette body **202**. The latching arrangement **240'** also includes a release handle **244'** that defines first and second ramped surfaces **272', 274'** that transition the stop members **242'** from lock positions to release positions.

(138) Each stop member **242'** includes a latching hook deflectable along the height H2 of the cassette body **202**. The first stop member **242'** extends rearwardly and defines a first engagement surface **246'** facing in the forwardly direction and the second stop member **242'** extends forwardly and defines a second engagement surface **248'** facing in the rearward direction. When the stop members **242'** align with the notch **166, 366** through the top **164, 364** of the guide **150, 350**, the first engagement surface **246'** abuts against the rearward-facing catch surface **170, 370** to inhibit movement of the cassette **200** relative to the guide **150, 350** in the forward direction. The second engagement surface **248'** abuts against the forward-facing catch surface **168, 368** to inhibit movement of the cassette **200** relative to the guide **150, 350** in the rearward direction.

(139) The release handle **244'** includes a transition arrangement **270'** that defines the first and second ramped surfaces **272', 274'**. In the example shown, the transition arrangement **270'** includes a protrusion extending outwardly from the release handle **244** away from the cassette body **202**. In other implementations, the protrusion may extend from the release handle **244** towards the cassette body **202**.

(140) Each latching hook defines a camming surface **252'** that seats on a respective one of the first and second ramped surfaces **272', 274'**. In the example shown, the tips of the latching hooks seat on the ramped surfaces **272', 274'**. When the release handle **244** is moved along the actuation axis A in the forward direction, the transition arrangement **270'** moves towards the first latching hook so that the camming surface **252'** of the first latching hook rides over the first ramped surface **272'**, thereby deflecting the first engagement surface **246'** to the release position. As the cassette body **202** begins to move forwardly relative to the guide **150, 350**, the camming surface **252'** of the second latching hook rides over the rearward-facing catch surface **170, 370** of the guide **150, 350**. Both latching hooks ride over the top **164, 364** of the guide **150, 350** in the release position as the cassette **200** is slid along the guide **150, 350**.

(141) Similarly, when the release handle **244** is moved along the actuation axis A in the rearward direction, the transition arrangement **270'** moves towards the second latching hook so that the camming surface **252'** of the second latching hook rides over the second ramped surface **274'**, thereby deflecting the second engagement surface **248'** to the release position. As the cassette body

202 begins to move rearwardly relative to the guide **150, 350**, the camming surface **252'** of the first latching hook rides over the forward-facing catch surface **168** of the guide **150, 350**. Both latching hooks ride over the top **164, 364** of the guide **150** in the release position as the cassette **200** is slid along the guide **150, 350**.

(142) Referring to the figures in general, some implementations of a cassette **200** are configured to receive a like number of plug connectors from the front and from the rear. Such cassettes **200** carry port members (e.g., optical adapters) only at the front end **204** of the cassette body **202**. Examples of such cassettes **200** are shown in FIG. **47** as cassette **200E** and FIG. **59** as cassette **200F**. The rear end **206** of the cassette body **202** defines a fiber port or cable port **284** through which fibers or one or more cables may extend into the cassette **200E, 200F**. The cassette **200E, 200F** may carry fiber management members **286** (e.g., a spool, a bend radius limiter, a retention finger, etc.) to facilitate routing fibers or cables between the front port members and the rear port **284**. The cassette **200E** of FIG. **47** includes a spool about which excess length of the fibers can be stored. The cassette **200F** of FIG. **59** is not configured to store excess length of the fibers.

(143) Connectorized ends of the fibers or cables routed into the cassette **200** can be plugged into rear ports defined by the forward port members. For example, a plurality of connectorized optical fibers can be plugged into rear ports of LC optical adapters **230** disposed at the front end **204** of the cassette **200** to mate with connectorized optical fibers plugged into front ports of the LC optical adapters **230**. In another example, a connectorized end of a multi-fiber cable can be plugged into a rear port of an MPO optical adapter disposed at the front end **204** of the cassette to mate with an MPO plug connector received at the front port.

(144) In some implementations, cassettes **200** connecting like numbers of plug connectors include a cover **262**. For example, a stub length of fibers or cable may be pre-terminated at the rear ports of the front port members and then routed out of the cassette **200** through the fiber or cable port **284**. In such examples, access to the rear ports of the front port members is not needed. The opposite end of the stub can be unterminated to facilitate splicing to one or more network cables. In other implementations, cassettes **200** connecting like numbers of plug connectors may have an open top that does not receive a cover (e.g., FIG. **47**). The open top may facilitate access to the rear ports of the front port members when stub fibers are not included with the cassette **200**. Rather, terminated ends of the network cables are routed directly to the front port members.

(145) In other implementations, the cassettes **200** are configured to connect unlike numbers of plug connectors. For example, a cassette **200** may carry one or more port members (e.g., single MPO adapters **232**) at the rear end **206** of the cassette body **202**. Media segments (e.g., optical fibers) extend between the rear port members and the front port members to form connections therebetween. In some implementations, the rear port members include multi-fiber optical adapters (e.g., MPO adapters) and the front port members include single-fiber optical adapters (e.g., LC adapters). In other implementations, the cassette **200** is configured to receive higher fiber count cables at the rear than at the front. For example, a twenty-four fiber MPO plug connector received at the rear end **206** of the cassette **200** may connect through the cassette **200** to three eight-fiber MPO plug connectors at the front, to twenty-four single-fiber LC plug connectors at the front, or to twelve dual-fiber SN plug connectors at the front.

(146) In certain implementations, the cassette body **202** defines one or more rear apertures **216** at the rear end **206** at which to receive the rear port members. In certain examples, each rear aperture **216** is configured to hold one or more multi-fiber optical adapters. In certain examples, each of the rear apertures **216** has a footprint sized to one standardized port. For example, each rear aperture **216** may receive an MPO optical adapter. In certain examples, the rear apertures **216** are sized smaller than the front apertures **212**. In an example, each cassette **200** has a single rear aperture **216**. In another example, each cassette **200** has two rear apertures **216**. In another example, each cassette **200** has three rear apertures **216**. In certain examples, each rear aperture **216** is sized to hold one standardized port. In certain implementations, a punch-out cover may be initially provided

at each of the rear apertures **216** so a respective optical adapter is mounted at fewer than all of the rear apertures **216**. In such cases, a user has the flexibility to select a position for a rear optical adapter to facilitate cable routing.

Aspects of the Disclosure

(147) Aspect 1. A communications arrangement comprising: a tray arrangement carrying a plurality of spaced apart guides extending parallel to each other along a forward-rearward axis of the tray arrangement; and a cassette configured to mount to the tray arrangement, the cassette carrying a plurality of port members, the cassette being sized to extend from a first guide, over a second guide, to a third guide, the cassette being configured to inter-connect with the first guide and the second guide, but not the third guide.

(148) Aspect 2. A communications arrangement comprising: a tray extending along a forward-rearward axis between opposite front and rear ends and along a lateral axis between opposite first and second sides carrying a plurality of guides spaced from each other along the lateral axis and extending generally parallel to each other, each of the guides extending along the forward-rearward axis, each of the guides defining a notch at a top of the guide; and a cassette mounted to the tray and selectively slidable along the forward-rearward axis, the cassette extending along the forward-rearward axis between opposite front and rear ends of the cassette and along the lateral axis between opposite first and second ends of the cassette, the cassette carrying a latching arrangement at the first end, the latching arrangement including a stop member aligned over the top of one of the guides when the cassette is mounted to the tray, the stop member riding over the top of the guide as the cassette is slid along the forward-rearward axis until the stop member aligns with the notch defined in the top of the guide, the stop member entering the notch when aligned with the notch along the forward-rearward axis to lock the cassette relative to the tray.

(149) Aspect 3. A communications arrangement comprising: a tray arrangement carrying a plurality of guides; the guides being configured to receive cassettes having widths of X and $1.5X$ without modifying the guides.

(150) Aspect 4. A communications arrangement comprising: a tray carrying a plurality of guides extending along a forward-rearward axis of the tray, the guides being parallel and spaced apart from each other along a lateral axis, each of the guides defining a groove facing in a first direction along the lateral axis, and each of the guides being devoid of grooves facing in an opposite second direction along the lateral axis; a first cassette mountable to the tray by engaging and sliding along first and second ones of the guides, the first and second guides being adjacent each other; and a second cassette mountable to the tray by engaging and sliding along third and fourth ones of the guides, the third and fourth guides being non-adjacent so that at least a fifth guide is disposed between the third and fourth guides along the lateral axis.

(151) Aspect 5. A communications arrangement comprising: a tray carrying a guide, the guide extending along a length between opposite first and second ends of the guide, the guide defining a groove extending along the length of the guide, the guide also extending between a bottom and a top, the bottom of the guide being configured to mount to the tray, the top of the guide defining a notch at an intermediate position between the first and second ends; a cassette extending along a length between opposite front and rear ends, along a width between opposite first and second ends, and along a height between a top and a bottom, the cassette including an end rail at the first side that is configured to slide along the groove defined by the guide, the cassette including a latching arrangement disposed at the first end above the end rail, the latching arrangement including: a stop member configured to move along the height of the cassette between a lock position and a release position; and a release handle that extends along the length of the cassette between opposite front and rear ends of the release handle so that the front end of the handle extends outwardly beyond the front end of the cassette and the rear end of the handle extends outwardly beyond the rear end of the cassette, the release handle being slidable along a forward-rearward axis relative to the cassette, the release handle being configured to transition the stop member from the lock position to the

release position.

(152) Aspect 6. A communications arrangement comprising: a tray extending along a forward-rearward axis between a front end and a rear end, the tray also extending along a lateral axis between opposite first and second sides; a plurality of guides mounted to the tray, the guides extending along lengths between opposite front and rear ends of the guides, the lengths of the guides being parallel to the forward-rearward axis of the tray, the guides being spaced apart along the lateral axis of the tray; a cassette configured to mount to the tray by sliding along first and second ones of the guides from either the front ends of the first and second guides or from the rear ends of the first and second guides at a discretion of a user, the cassette including a locking arrangement configured to lock to the first guide to maintain the cassette in position relative to the first guide, the cassette carrying a release handle that moves relative to the cassette along an actuation axis that extends parallel to the forward-rearward axis of the tray, the release handle releasing the locking arrangement from the first guide when moved along the actuation axis in a forward direction or a rearward direction at the discretion of the user.

(153) Aspect 7. A communications arrangement comprising: a tray extending along a forward-rearward axis and along a lateral axis that is orthogonal to the forward-rearward axis, the tray defining a row of bays extending along the lateral axis, each of the bays extending along a width between an engagement end of a first guide and a non-engagement end of a second guide that is adjacent the first guide, the width extending along the lateral axis; a plurality of cassettes each configured to mount to the tray across a respective plurality of the bays, each cassette being configured to slide over the respective plurality of bays along the forward-rearward axis of the tray, each cassette including first and second engagement members that inter-connect with the engagement ends of first and second guides, wherein the cassette does not inter-connect with the non-engagement ends of the guides.

(154) Aspect 8. A communications cassette comprising: a body extending along a length between opposite front and rear ends, along a width between opposite first and second ends, and along a height between a top and a bottom, the body including a latching arrangement disposed at the first end of the body, the latching arrangement including: a stop member configured to move along the height of the body between a lock position and a release position; and a release handle that extends along the length of the body between opposite front and rear ends of the release handle so that the front end of the release handle extends outwardly beyond the front end of the body and the rear end of the release handle extends outwardly beyond the rear end of the body, the release handle being slidable along a forward-rearward axis relative to the body, the release handle being configured to transition the stop member from the lock position to the release position.

(155) Aspect 9. A communications cassette comprising: a body having a width extending between opposite first and second ends of the body and a depth extending between opposite front and rear ends of the body; a row of optical adapters carried at the front end of the body so that front ports of the optical adapters are accessible from the front end of the body; an end rail disposed at the first end of the body; and a bottom rail disposed at an intermediate position between the first and second ends of the body, the bottom rail having a common orientation with the end rail; the body being devoid of rails at the second end of the body.

(156) Aspect 10. A tray arrangement extending along a lateral axis between opposite first and second ends, along a forward-rearward axis between opposite front and rear ends, and along a height between a bottom and a top, the tray arrangement comprising: a tray having a forward end portion towards the front end of the tray arrangement, a rearward end portion toward the rearward end of the tray arrangement, and an intermediate portion disposed between the forward end portion and the rearward end portion along the forward-rearward axis, the intermediate portion being raised along the height of the tray arrangement relative to the forward end portion; and a plurality of guides extending across the intermediate portion along the forward-rearward axis, each of the guides being mounted to the forward end portion of the tray and to the rearward end portion of the

tray, each of the guides extending partially over the forward end portion and partially over the rearward end portion.

(157) Aspect 11. A tray arrangement comprising: a tray extending along a forward-rearward axis and along a lateral axis that is orthogonal to the forward-rearward axis; and a plurality of guides mounted to the tray, the guides being configured to slidably receive a plurality of cassettes along the forward-rearward axis, the guides being parallel to each other and spaced apart along the lateral axis so that the plurality of cassettes includes a plurality of base-8 cassettes or a plurality of base-12 cassettes at a discretion of the user without modifying a spacing between the guides, the base-12 cassette being wider than the base-8 cassette.

(158) Aspect 12. A tray arrangement comprising: a tray extending along a forward-rearward axis and along a lateral axis that is orthogonal to the forward-rearward axis; and a plurality of guides mounted to the tray, each of the guides having an L-shaped transverse cross-sectional profile.

(159) Aspect 13. A communications panel comprising: a chassis defining an interior; a tray arrangement configured to mount within the interior of the chassis, the tray arrangement extending along a forward-rearward axis between opposite front and rear ends and along a lateral axis between opposite first and second sides carrying a plurality of guides spaced from each other along the lateral axis and extending generally parallel to each other, each of the guides extending along the forward-rearward axis, each of the guides defining a notch at a top of the guide; and a cassette mounted to the tray arrangement and selectively slidable along the forward-rearward axis, the cassette extending along the forward-rearward axis between opposite front and rear ends of the cassette and along the lateral axis between opposite first and second ends of the cassette, the cassette carrying a latching arrangement at the first end, the latching arrangement including a stop member aligned over the top of one of the guides when the cassette is mounted to the tray, the stop member riding over the top of the guide as the cassette is slid along the forward-rearward axis until the stop member aligns with the notch defined in the top of the guide, the stop member entering the notch when aligned with the notch along the forward-rearward axis to lock the cassette relative to the tray.

(160) Aspect 14. A communications panel system comprising: a chassis defining an interior extending along a forward-rearward axis between opposite front and rear ends of the chassis and along a lateral axis between opposite first and second ends of the chassis; a tray mountable within the interior of the chassis through the front end, the tray carrying a plurality of guides spaced apart from each other along the lateral axis, each of the guides extending along the forward-rearward axis; a plurality of cassettes configured to slide along the guides to mount to the tray, each of the cassettes extending along a width between opposite first and second ends, the first end of each cassette carrying an end rail configured to inter-connect with a respective first one of the guides, an intermediate portion of the cassette carrying a bottom rail configured to inter-connect with a respective second one of the guides, the end rail and the bottom rail extending outwardly in a common direction from a base end contacting the cassette to a free end.

(161) Aspect 15. A method of removing a cassette from a tray having a plurality of parallel guides each extending parallel to a forward-rearward axis of the tray, the cassette being slidable along the tray relative to the guides, each cassette carrying a release handle, the method comprising: choosing one of a forward direction and a rearward direction along which to remove the cassette from the tray; pulling the release handle relative to the cassette in the chosen direction to unlatch the cassette from a first of the guides; and continuing to pull the release handle in the chosen direction to slide the cassette in the chosen direction relative to the first guide.

(162) Aspect 16. A tray arrangement extending along a lateral axis between opposite first and second ends, along a forward-rearward axis between opposite front and rear ends, and along a height between a bottom and a top, the tray arrangement comprising: a tray having opposite top and bottom surfaces each extending along the lateral axis and the forward-rearward axis, the tray defining a main region at which a plurality of apertures are defined, each of the apertures extending

between the top and bottom surfaces; and a plurality of guides heat attached the tray at the main region, each of the guides including a plurality of pegs extending into respective ones of the apertures defined in the tray, each of the guides defining a grooved side facing towards the first end of the tray arrangement and a closed side facing towards the second end of the tray arrangement.

(163) Aspect 17. A tray arrangement extending along a lateral axis between opposite first and second ends, along a forward-rearward axis between opposite front and rear ends, and along a height between a bottom and a top, the tray arrangement comprising: a tray; and a plurality of guides mounted to the tray, each of the guides extending along the forward-rearward axis, the guides being spaced from each other along the lateral axis, the guides including a first guide and a second guide connected by a webbing so that the first and second guides mount to the tray as a unit.

(164) Aspect 18. A method of manufacturing a plurality of tray arrangements, the method comprising: selecting one of a first tray arrangement and a second tray, each of the first and second trays defining a plurality of apertures, each of the first and second trays defining countersinks, the first tray having a different thickness than the second tray so that the apertures of the first tray have a different height than the apertures of the second tray; mounting a plurality of guides to the selected one of the first and second trays, the guides each having a plurality of pegs, wherein mounting the guides includes inserting the pegs into the apertures of the selected one of the first and second trays, wherein the pegs of the guides have a common size regardless of which of the first and second trays is selected; and liquefying at least portions of the pegs into the countersinks.

(165) Aspect 19. A communications arrangement comprising: a tray arrangement carrying a plurality of guides spaced apart from each other along a lateral axis of the tray arrangement, each of the guides extending along a forward-rearward axis of the tray arrangement; a plurality of cassettes mounted to the tray arrangement in a row along the lateral axis of the tray arrangement, each of the cassettes defining a plurality of front apertures each configured to receive at least one port member, the front apertures of each cassette being spaced from each other along the lateral axis of the tray arrangement by a first gap, wherein the cassettes are configured so that adjacent front apertures of adjacent cassettes on the tray arrangement are separated from each other by a second gap that is about equal to the first gap.

(166) Having described the preferred aspects and implementations of the present disclosure, modifications and equivalents of the disclosed concepts may readily occur to one skilled in the art. However, it is intended that such modifications and equivalents be included within the scope of the claims which are appended hereto.

Claims

1. A tray arrangement extending along a lateral axis between opposite first and second ends, along a forward-rearward axis between opposite front and rear ends, and along a height between a bottom and a top, the tray arrangement comprising: a tray having opposite top and bottom surfaces each extending along the lateral axis and the forward-rearward axis, the tray defining a main region at which a plurality of apertures are defined, each of the apertures extending between the top and bottom surfaces; and a plurality of guides attached to the tray at the main region, each of the guides including a plurality of pegs extending into respective ones of the apertures defined in the tray, each of the guides defining a grooved side facing towards the first end of the tray arrangement and a closed side facing towards the second end of the tray arrangement.
2. The tray arrangement of claim 1, wherein each guide extends along a length from a respective first end to a respective second end.
3. The tray arrangement of claim 2, wherein the grooved side defines a groove that extends along the length between the first and second ends.
4. The tray arrangement of claim 2, wherein the grooved side is partially defined by a top surface

extending along the length of the guide, the top surface defining a ramped surface at the first and second ends.

5. The tray arrangement of claim 4, wherein the top surface defines a notch at an intermediate position between the first and second ends, the notch providing access to the grooved side through the top surface.

6. The tray arrangement of claim 5, wherein the notch provides access to a forward-facing catch surface and a rearward-facing catch surface at opposite ends of the notch.

7. The tray arrangement of claim 1, wherein the grooved side defines a notch at an intermediate position between the first and second ends.

8. The tray arrangement of claim 7, wherein the notch provides access to a forward-facing catch surface and a rearward-facing catch surface at opposite ends of the notch.

9. The tray arrangement of claim 1, wherein each of the guides has an L-shaped transverse cross-section.

10. The tray arrangement of claim 1, wherein each of the guides has a C-shaped transverse cross-section.

11. The tray arrangement of claim 1, wherein the tray arrangement is configured to mount to a chassis and to move relative to the chassis between a retracted position and an extended position.

12. The tray arrangement of claim 1, wherein the pegs are heat-staked to the tray.

13. The tray arrangement of claim 1, wherein the tray defines a plurality of finger access openings disposed forward of the main region of the tray.

14. The tray arrangement of claim 1, wherein the apertures lead to countersinks at the bottom surface of the tray.

15. The tray arrangement of claim 1, wherein the apertures are aligned in rows.

16. The tray arrangement of claim 15, wherein one or more of the apertures in a first of the rows are laterally offset from each other.

17. The tray arrangement of claim 16, wherein front and rear ones of the apertures of the first row are aligned along a reference axis while intermediate ones of the apertures of the first row are offset along the lateral axis relative to the reference axis.

18. The tray arrangement of claim 1, wherein a first of the guides includes a side tab extending outwardly from the grooved side.

19. The tray arrangement of claim 7, wherein a first of the guides includes a side tab extending outwardly from the grooved side, the side tab aligning with the notch.

20. The tray arrangement of claim 1, wherein the guide is configured to engage with a cassette at only the grooved side.
