

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250286033

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

CHI; Xiao et al.

DISPLAY PANEL AND DISPLAY DEVICE

Abstract

Provided are display panel and display device. Display panel includes base substrate; light-emitting element located on base substrate; first electrode and second electrode both electrically connected to light-emitting element, both located on side of light-emitting element facing base substrate or on side of light-emitting element facing away from base substrate and both providing voltage signals for light-emitting element; first reflective layer located on side of light-emitting element facing base substrate, and with direction perpendicular to base substrate as projection direction, first reflective layer covering light-emitting element; and voltage signal line located on side of light-emitting element facing base substrate. First electrode and second electrode respectively include first extension part and second extension part, at least one of which is connected to voltage signal line and does not overlap first reflective layer. First electrode and second electrode normally receive voltage signals, and light-emitting efficiency of display panel is improved.

Inventors: CHI; Xiao (Shanghai, CN), FU; Jujian (Shanghai, CN), AN; Ping (Shanghai, CN)

Applicant: Shanghai Tianma Micro-Electronics Co., Ltd. (Shanghai, CN)

Family ID: 75651572

Assignee: Shanghai Tianma Micro-Electronics Co., Ltd. (Shanghai, CN)

Appl. No.: 19/215266

Filed: May 21, 2025

Foreign Application Priority Data

CN 202110157343.9

Feb. 04, 2021

CN 202110231403.7

Mar. 02, 2021

Related U.S. Application Data

parent US continuation 17512689 20211028 parent-grant-document US 12341140 child US

Publication Classification

Int. Cl.: **H01L25/16** (20230101); **H10D86/40** (20250101); **H10D86/60** (20250101); **H10H20/856** (20250101); **H10H20/857** (20250101)

U.S. Cl.:

CPC **H01L25/167** (20130101); **H10D86/441** (20250101); **H10D86/60** (20250101); **H10H20/856** (20250101); **H10H20/857** (20250101);

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) [0001] This is a continuation of U.S. patent application Ser. No. 17/512,689, filed on October. 28, 2021, which claims priority to Chinese Patent Application No. 202110231403.7, titled “DISPLAY PANEL AND DISPLAY DEVICE” filed Mar. 2, 2021, which claims priority to the Chinese Patent Application No. 202110157343.9, titled “DISPLAY PANEL AND ELECTRICAL DEVICE” filed Feb. 4, 2021, the disclosures of which are incorporated herein by reference in their entireties.

FIELD

[0002] The present disclosure relates to the field of display technologies and, in particular, to a display panel and a display device including the display panel.

BACKGROUND

[0003] In recent years, the display industry has entered a stage of rapid development. The display panel have gradually developed from a liquid crystal display panel to a self-luminous light-emitting panel such as an organic light-emitting display panel and a micro light-emitting diode (micro LED) display panel. The self-luminous light-emitting panel has many advantages such as a simple structure, a high light-emitting efficiency, flexibility, and lightness and thinness and thus is widely favored by consumers. In particular, since the light-emitting element of the micro LED display panel is the micro LED and has advantages such as relatively high light-emitting brightness and relatively low power consumption, the micro LED display panel has gradually become a hotspot in the industry.

[0004] Since the micro LED emits light uniformly in all directions, to achieve high brightness of the display panel, a special design is needed to focus the light emitted by the micro LED toward a light-emitting side of the display panel, to increase the light-emitting efficiency of the display panel as much as possible. Based on this, how to arrange a reasonable structure to increase the light-emitting efficiency of the display panel while the normal function of the display panel is ensured is a problem to be solved urgently in the field.

SUMMARY

[0005] In view of the above, the present application provides a display panel and a display device, to increase the light-emitting efficiency of the display panel while ensuring the normal function of the display panel, by arranging a reasonable reflection structure.

[0006] In an aspect, embodiments of the present application provide a display panel. The display panel includes a base substrate, a light-emitting element, a first electrode and a second electrode, a first reflective layer, and a pixel circuit. The light-emitting element is located on a side of the base substrate. The first electrode and the second electrode are electrically connected to the light-emitting element, and are both located on a side of the light-emitting element facing the base

substrate or both located on a side of the light-emitting element facing away from the base substrate. The first reflective layer is located on a side of the light-emitting element facing the base substrate, and with a direction perpendicular to the base substrate as a projection direction, the first reflective layer covers the light-emitting element. The pixel circuit is electrically connected to the light-emitting element, and the pixel circuit includes a first transistor and a second transistor. With the direction perpendicular to the base substrate as the projection direction, at least one of the first transistor or the second transistor does not overlap the first reflective layer.

[0007] In another aspect, embodiments of the present application further provide a display device. The display device includes a display panel. The display panel includes a base substrate, a light-emitting element, a first electrode and a second electrode, a first reflective layer, and a pixel circuit. The light-emitting element is located on a side of the base substrate. The first electrode and the second electrode are electrically connected to the light-emitting element, and are both located on a side of the light-emitting element facing the base substrate or both located on a side of the light-emitting element facing away from the base substrate. The first reflective layer is located on a side of the light-emitting element facing the base substrate, and with a direction perpendicular to the base substrate as a projection direction, the first reflective layer covers the light-emitting element. The pixel circuit is electrically connected to the light-emitting element, and the pixel circuit includes a first transistor and a second transistor. With the direction perpendicular to the base substrate as the projection direction, at least one of the first transistor or the second transistor does not overlap the first reflective layer.

Description

BRIEF DESCRIPTION OF DRAWINGS

[0008] FIG. 1 is a partial schematic view of a display panel according to an embodiment of the present application;

[0009] FIG. 2 is a top view of the display panel of FIG. 1;

[0010] FIG. 3 is a partial schematic view of a display panel according to another embodiment of the present application;

[0011] FIG. 4 is a partial top view of a display panel according to another embodiment of the present disclosure;

[0012] FIG. 5 is a partial schematic view of a display panel according to another embodiment of the present application;

[0013] FIG. 6 is a partial schematic view of a display panel according to another embodiment of the present application;

[0014] FIG. 7 is a partial schematic view of a display panel according to another embodiment of the present application;

[0015] FIG. 8 is a partial schematic view of a display panel according to another embodiment of the present application;

[0016] FIG. 9 is a partial schematic view of a display panel according to another embodiment of the present application;

[0017] FIG. 10 is a partial schematic view of a display panel according to another embodiment of the present application;

[0018] FIG. 11 is a partial schematic view of a display panel according to another embodiment of the present application;

[0019] FIG. 12 is a partial schematic view of a display panel according to another embodiment of the present application;

[0020] FIG. 13 is a partial schematic view of a display panel according to another embodiment of the present application;

[0021] FIG. **14** is a partial schematic view of a display panel according to another embodiment of the present application;

[0022] FIG. **15** is a partial schematic view of a display panel according to another embodiment of the present application;

[0023] FIG. **16** is a partial schematic view of a display panel according to another embodiment of the present application;

[0024] FIG. **17** is a partial schematic view of a display panel according to another embodiment of the present application;

[0025] FIG. **18** is a top view of voltage signal lines according to an embodiment of the present application;

[0026] FIG. **19** is a partial schematic view of a display panel according to another embodiment of the present application;

[0027] FIG. **20** is a schematic diagram of a light-emitting element according to an embodiment of the present disclosure;

[0028] FIG. **21** is a schematic diagram of another light-emitting element according to an embodiment of the present disclosure;

[0029] FIG. **22** is a schematic diagram of another light-emitting element according to an embodiment of the present disclosure;

[0030] FIG. **23** is a partial top view of a display panel according to another embodiment of the present disclosure;

[0031] FIG. **24** is a partial top view of a display panel according to another embodiment of the present disclosure;

[0032] FIG. **25** is a partial schematic view of a display panel according to another embodiment of the present application;

[0033] FIG. **26** is a partial schematic view of a display panel according to another embodiment of the present application;

[0034] FIG. **27** is a partial schematic view of a display panel according to another embodiment of the present application;

[0035] FIG. **28** is a partial top view of a display panel according to another embodiment of the present disclosure;

[0036] FIG. **29** is a partial schematic view of a display panel according to another embodiment of the present application;

[0037] FIG. **30** is a partial schematic view of a display panel according to another embodiment of the present application; and

[0038] FIG. **31** is a schematic diagram of a display device according to an embodiment of the present application.

DETAILED DESCRIPTION

[0039] Embodiments of the present disclosure are described below in conjunction with drawings and embodiments.

[0040] It is to be noted that details are set forth below to facilitate a thorough understanding of the present disclosure. However, the present disclosure may be implemented by various embodiments different from the embodiments described herein. Therefore, the present disclosure is not limited to the embodiments disclosed below.

[0041] In one aspect, embodiments of the present application provide a display panel. Referring to FIGS. **1** to **3**, FIG. **1** is a partial schematic view of a display panel according to an embodiment of the present application, FIG. **2** is a top view of the display panel of FIG. **1**, FIG. **1** is a sectional view taken along a direction AA' of FIG. **2**, and FIG. **3** is a partial schematic view of a display panel according to another embodiment of the present application. A display panel **10** includes a base substrate **100**, a light-emitting element **200**, a first electrode **101** and a second electrode **102**, a first reflective layer **103**, and a voltage signal line **300**. The light-emitting element **200** is located on

the base substrate **100**. The first electrode **101** and the second electrode **102** are electrically connected to the light-emitting element **200**. Moreover, as shown in FIG. **1**, the first electrode **101** and the second electrode **102** are both located on a side of the light-emitting element **200** facing the base substrate **100**, or as shown in FIG. **3**, the first electrode **101** and the second electrode **102** are both located on a side of the light-emitting element **200** facing away from the base substrate **100**, and the first electrode **101** and the second electrode **102** provide voltage signals for the light-emitting element **200**. The first reflective layer **103** is located on a side of the light-emitting element **200** facing the base substrate **100**, and with a direction perpendicular to the base substrate **100** as a projection direction, the first reflective layer **103** covers the light-emitting element **200**. The voltage signal line **300** is located on a side of the light-emitting element **200** facing the base substrate **100**. The first electrode **101** includes a first extension part **1011**, and the second electrode **102** includes a second extension part **1022**. The first extension part **1011** and the second extension part **1022** are connected to the voltage signal line **300**. With the direction perpendicular to the base substrate **100** as the projection direction, at least one of the first extension part **1011** or the second extension part **1022** does not overlap the first reflective layer **103**.

[0042] In the present application, the light-emitting element **200** may be a micro LED light-emitting element, a nanorod light-emitting diode (nanorod LED) light-emitting element, or other types of LED light-emitting elements. The light-emitting element **200** may include a P-type region and an N-type region. The P-type region and the N-type region are electrically connected to respective voltage signal lines through electrodes, to control the light-emitting element to be ON or to be OFF. In the present application, the voltage signal line **300** is a generic term for the voltage signal line connected to the first electrode **101** and the voltage signal line connected to the second electrode **102**. It does not mean that only one voltage signal line exists, and it does not mean that the first electrode **101** and the second electrode **102** are connected to a same voltage signal line. Each of the first electrode **101** and the second electrode **102** may be connected to a respective voltage signal line. The first electrode **101** is electrically connected to a respective voltage signal line through the first extension part **1011**, and a connection manner there between may be a direct connection or an electrical connection through a via hole. The second electrode **102** is electrically connected to a respective voltage signal line through the second extension part **1022**, and the connection manner there between may be a direct connection or an electrical connection through a via hole. As shown in FIGS. **1** and **3**, the connection manners therein are all in a connection through a via hole.

[0043] It is to be noted that, as described above, the first reflective layer **103** covers the light-emitting element **200**, which generally indicates that with the direction perpendicular to the base substrate **100** as the projection direction, the projection of the first reflective layer **103** covers the projection of the light-emitting element **200**. Such coverage herein is generally referred as a full coverage, that is, the projected area of the first reflective layer **103** is greater than or equal to the projected area of the light-emitting element **200**. In such a way, the first reflective layer **103** may reflect as much light as possible emitted by the light-emitting element **200** to the backlight side to a light-emitting side, so that the light-emitting efficiency is increased. However, in some special cases, the specific designs are considered, for example, a partial region, such as positions of some holes or the positions of some special structures both of which need to be avoided from being covered, of the light-emitting element **200** cannot be covered by the first reflective layer **103**, which also falls within the scope of “coverage” defined by the present application. That is, the term “coverage”, if no special cases exist, may refer to a full coverage, but if a special structural design exists, may also refer to an at least partial coverage.

[0044] In addition, the first reflective layer **103** in this embodiment mainly plays a role of reflecting light, and the material of the first reflective layer **103** may be a metal material such as silver, aluminum, titanium, or molybdenum, or may be an alloy material containing silver, aluminum, titanium, or molybdenum, or the material of the first reflective layer **103** may be a fluorescent

material or other materials with a light-reflecting property, which is not limited in this embodiment. [0045] Based on the preceding description, in the present application, at least one of the first extension part **1011** or the second extension part **1022** does not overlap the first reflective layer **103**. On the one hand, the light-emitting efficiency of the display panel is improved. On the other aspect, the inventor of the present application found that the first extension part **1011** and the second extension part **1022** needs to be connected to the voltage signal line **300** on a side facing the base substrate, however as the first reflective layer **103** covers the light-emitting element **200**, the first reflective layer **103** may block the connection between the first extension part **1011** and the voltage signal line **300** and may block the connection between the second extension part **1022** and the voltage signal line **300**. Therefore, at least one of the first extension part **1011** and the second extension part **1022** is arranged to not overlap the first reflective layer **103**, so that the introduction of the first reflective layer **103** can be prevented from affecting the voltage signal input on the first electrode **101** and the second electrode **102**.

[0046] In an embodiment, as shown in FIG. 1, in this embodiment, the voltage signal line **300** includes a first voltage signal line **301** that provides a first voltage signal and a second voltage signal line **302** that provides a second voltage signal. The first electrode **101** receives the first voltage signal, the second electrode **102** receives the second voltage signal, and the voltage of the first voltage signal is higher than the voltage of the second voltage signal. The display panel includes a pixel circuit **400**, and a pixel circuit **400** is connected to the first voltage signal line **301**. In a light emission stage of the display panel, the first extension part **1011** receives the first voltage signal through a transistor of the pixel circuit **400**; the second extension part **1022** is connected to the second voltage signal line **302** and is configured to receive the second voltage signal.

[0047] In one embodiment, the pixel circuit **400** may include a transistor. T transistor includes a gate **401**, an active layer **402**, a source **403**, and a drain **404**. A voltage signal is transmitted between the source **403** and the drain **404** in the case where the transistor is turned on. The pixel circuit **400** generally receives signals such as the first voltage signal, a data write signal, and a reset signal. Under the control of a gate drive signal and a light emission control signal, a drive current is selectively provided for the light-emitting element **200**. The transistor in the pixel circuit **400** include a drive transistor and a switching transistor. The switching transistor is mainly responsible for selectively providing various signals for the drive transistor, and the drive transistor is mainly responsible for generating a drive current for the light-emitting element. The transistor of the pixel circuit **400** may be a silicon-based transistor such as a transistor formed with low-temperature polycrystalline silicon (LTPS) as an active layer and may also be an oxide semiconductor-based transistor, which is a transistor formed with an oxide semiconductor as an active layer such as an indium gallium zinc oxide (IGZO) type transistor. In some cases, at least one transistor in the pixel circuit **400** may be an LTPS type transistor, and at least one transistor may be an IGZO type transistor. In addition, as shown in FIG. 1, the display panel further includes insulating layers such as an insulating layer **110**, an insulating layer **111**, an insulating layer **112**, an insulating layer **113**, an insulating layer **114**, an insulating layer **115**, and so on. These insulating layers mainly isolate conductive layers to prevent the signal confusion caused by the mutual connection between the conductive layers. In a case where the upper conductive layers and the lower conductive layers need to be connected, via holes are disposed on the insulating layers to achieve electrical connection.

[0048] In this embodiment, the light-emitting element **200** may be a micro LED light-emitting element or a nanorod LED light-emitting element. The light-emitting element **200** includes a P-type region and an N-type region. The P-type region is connected to the first electrode **101** so that the first voltage signal is received, and the N-type region is connected to the second electrode **102** so that the second voltage signal is received. In one embodiment, the first voltage signal may be a high voltage signal, the second voltage signal may be a low voltage signal so that a potential difference is formed between the high voltage signal and the low voltage signal, and thus the LED

emits light under the action of the potential difference. In this embodiment, the first voltage signal is selectively transmitted to the first electrode **301** through the pixel circuit **400**, and the second voltage signal is transmitted to the second electrode **302** through an electrical connection so that a light-emitting brightness of the light-emitting element **200** may be controlled.

[0049] Based on the preceding setting, in this embodiment, at least the first extension part **101** and the first reflective layer **103** do not overlap. As described above, the first extension part **1011** is connected to the first voltage signal line **301** through the transistors in the pixel circuit **400**, and the second extension part **1022** may be electrically connected to the second voltage signal line **302** through a via hole or directly connected to the second voltage signal line **302**. However, as described above, each transistor in the pixel circuit **400** includes the gate **401**, the active layer **402**, the source **403**, the drain **404**, and insulating layers and often needs to occupy more film layers. Therefore, whether the first reflective layer **103** affects the connection between the first extension part and the transistor must be considered. To ensure the connection between the first extension part and the transistor, the first extension part **1011** is arranged to not overlap the first reflective layer **103**, which is conducive to achieving a connection between the first extension part **1011** and the transistors in a region where the first extension part **1011** does not overlap the first reflective layer **103**.

[0050] Referring to FIG. 4, FIG. 4 is a partial top view of a display panel according to another embodiment of the present disclosure. A length L1 of the first extension part **1011** is greater than a length L2 of the second extension part **1022**. Herein, the length L1 of the first extension part **1011** and the length L2 of the second extension part **1022** generally refer to a length of the first extension part **1011** and a length of the second extension part **1022** relative to the extension direction of the light-emitting element **200**. As described above, the first extension part **1011** is connected to the transistors of the pixel circuit **400**, the transistors generally occupy more film layers, and both the film layers of the transistors and the film layer of the first reflective layer **103** are located on a side of the light-emitting element **200** facing the base substrate. Therefore, the influence of the first reflective layer **103** on the connection between the first extension part **1011** and the transistors must be considered. To ensure that the first reflective layer **103** fully plays the role of reflecting, the area of the first reflective layer **103** is generally greater than the area of the light-emitting element **200**. Therefore, in this embodiment, the length of the first extension part **1011** may be appropriately set to be relatively longer so that the connection between the first extension part **1011** and the transistors is ensured, as long as the second extension part **1022** is electrically connected to the second voltage signal line **302**. Generally speaking, the second voltage signal line **302** may be a conductive layer and may be located on a side of the first reflective layer **103** facing away from the base substrate, or may be located on a side of the first reflective layer **103** facing the base substrate, or may be located on a same layer as the first reflective layer **103**. In particular, in a case where the second voltage signal line **302** is located on a side of the first reflective layer **103** facing away from the base substrate or on a same layer as the first reflective layer **103**, the connection between the second extension part **1022** and the second voltage signal line **302** does not need to avoid the first reflective layer **103**. Therefore, the second extension part **1022** may be set to be relatively shorter so that a panel space may be saved. In a case where the second voltage signal line **302** is located on a side of the first reflective layer **103** facing the base substrate, since the second voltage signal line **302** is generally a single conductive layer or may be double conductive layers, an adjustment of a position of the second voltage signal line **302** is relatively easy compared with an adjustment of multi-layered transistors. For example, the gate, the active layer, the source, the drain, and so on need to be considered for the adjustment of the film layers of the transistors, and changes in the size or relative position of the gate, the active layer, the source, the drain, and so on may possibly cause changes in an aspect ratio, a threshold voltage, and other parameters of the transistor. To sum up, when saving the panel space is considered, the second extension part **1022** connected to the second voltage signal line **302** whose position may be relatively easily adjusted, may be

appropriately set to be relatively shorter, and the length of the first extension part **1011** may be set to be relatively longer so that characteristics of respective connection structures may be better matched.

[0051] Referring to FIG. 5, FIG. 5 is a partial schematic view of a display panel according to another embodiment of the present application. The pixel circuit **400** includes a first transistor **410** and a second transistor **420**. The first transistor **410** includes a first gate **411**, a first active layer **412**, a first source **413**, and a first drain **414**. The second transistor **420** includes a second gate **421**, a second active layer **422**, a second source **423**, and a second drain **424**. The first extension part **1011** is connected to the first drain **414**, and at least part of the structure of the first transistor **410** is located on a side of the first reflective layer **103** facing the base substrate **100**. Since the first reflective layer **103** mainly plays the role of reflecting the light emitted by the light-emitting element **200** to the backlight side to the light-emitting side, to avoid light loss, the distance between the first reflective layer **103** and the light-emitting element **200** should not be too great. In a case where the distance is too far, the insulating layers in the middle absorb more in the light path where the light is reflected back and forth, resulting in more light loss, which affects the light-emitting efficiency. Therefore, generally speaking, at least part of the structure of the first transistor **410** is located on a side of the first reflective layer **103** facing the base substrate **100**. In such a way, the first reflective layer **103** may be prevented from being too far away from the light-emitting element **200**. Based on this structure, if the first extension part **1011** is connected to the first transistor **410**, the first extension part **1011** and the first reflective layer **103** do not overlap so that the first reflective layer **103** may be prevented from affecting the connection between the first extension portion **1011** and the first transistor **410**.

[0052] In an embodiment, referring to FIG. 5, in this embodiment, with the direction perpendicular to the base substrate **100** as the projection direction, both the first transistor **410** and the second transistor **420** do not overlap the first reflective layer **103**, and the first reflective layer **103** and at least one of the first gate **411** or the second gate **421** are located on a same layer. In this case, since neither the first transistor **410** nor the second transistor **420** does not overlap the first reflective layer **103**, the first reflective layer **103** needs to be located on a side of the light-emitting element **200** facing the base substrate **100**, and the first gate **411** and the second gate **421** are generally made of metal materials, which are also reflective materials. Therefore, from the perspective of simplifying the process, the first reflective layer **103** is located on a same layer as the first gate **411** or the second gate **421**. In particular, in a case where the material of the first reflective layer **103** is same as the material of the first gate **411** or the second gate **421**, the first reflective layer **103** may be made of the same material in a same process with the first gate **411** or the second gate **421**, to simplify the process, reducing the thickness of the display panel, and simplifying the overall structure.

[0053] In an embodiment, referring to FIG. 6, FIG. 6 is a partial schematic view of a display panel according to another embodiment of the present application. In the figure, with the direction perpendicular to the base substrate **100** as the projection direction, at least one of the first transistor **410** or the second transistor **420** and the light-emitting element **200** overlap, and at least one of the first gate **411** or the second gate **421** is multiplexed as the first reflective layer **103**. In a case where the panel has a relatively high resolution requirement, a situation where the transistors in the pixel circuit **400** overlaps the light-emitting element **200** may exist. In this situation, the gate of the transistor that overlaps the light-emitting element **200** may be multiplexed as the first reflective layer **103**. FIG. 6 shows a situation where the first transistor **410** overlaps the light-emitting element **200**. In this situation, the first gate **411** is multiplexed as the first reflective layer **103**; in a case where the second transistor **420** overlaps the light-emitting element **200**, the second gate **421** is multiplexed as the first reflective layer **103**. In such a way, on the one hand, the first gate **411** or the second gate **421** is used as a gate by using the electrical characteristic of the first gate **411** or the second gate **421**; on the other hand, the first gate **411** or the second gate **421** is used as the first

reflective layer **103** by using the reflective property of the metal material of which the first gate **411** or the second gate **421** is made so that the first gate **411** and the second gate **421** are fully utilized, which is conducive to simplifying the structure of the panel and achieving the high-resolution display.

[0054] In an embodiment, referring to FIG. 7, FIG. 7 is a partial schematic view of a display panel according to another embodiment of the present application. In the figure, the first reflective layer **103** is located on a side of the first gate **411** and the second gate **421** facing away from the base substrate. It is to be noted herein that both the first transistor **410** and the second transistor **420** may overlap the light-emitting element **200**, or one of the first transistor **410** and the second transistor **420** may overlap the light-emitting element **200**, or neither the first transistor **410** nor the second transistor **420** may overlap the light-emitting element **200**. Herein, the first reflective layer **103** is disposed on a side of the first gate **411** and the second gate **421** facing away from the base substrate based on the role played by the first reflective layer **103** to reflect the light of the light-emitting element **200**. In a case where the first reflective layer **103** is not located on a same layer as the first gate **411** and the second gate **421**, to fully ensure the reflection effect of the first reflective layer **103**, the first reflective layer **103** is disposed on the side of the first gate **411** and the second gate **421** facing away from the base substrate.

[0055] In an embodiment, referring to FIGS. 8 and 9, FIG. 8 is a partial schematic view of a display panel according to another embodiment of the present application, and FIG. 9 is a partial schematic view of a display panel according to another embodiment of the present application. The first active layer **412** includes silicon, the second active layer **422** includes an oxide semiconductor, the second active layer **422** is located on a side of the first active layer **412** facing away from the base substrate **100**, and the second gate **421** is located on a side of the second active layer **422** facing away from the base substrate **100**. As shown in FIG. 8, the first reflective layer **103** and the second gate **421** are located on the same layer, or as shown in FIG. 9, the second gate **421** is multiplexed as the first reflective layer **103**. Since the LTPS type transistor has advantages such as a strong driving ability and relatively high stability, the LTPS type transistor may be used as a drive transistor or a switching transistor in the pixel circuit. The IGZO type transistor has advantages such as a small leakage current and may be applied to an important switching transistor so that the leakage current is reduced. Therefore, the pixel circuit **400** may include both LTPS type transistors and IGZO type transistors. In this case, generally speaking, the active layer of the IGZO type transistor is more sensitive to hydrogen elements, and after the LTPS type active layer is formed, the IGZO type active layer is manufactured. Therefore, the second active layer **422** is located on a side of the first active layer **412** facing away from the base substrate **100**, and the IGZO type active layer is generally manufactured as a top-gate structure or a top-bottom double-gate structure. As described above, in the case where the first reflective layer **103** is relatively close to the light-emitting element **200**, the first reflective layer **103** has a better reflection effect. Therefore, in conjunction with the light-emitting efficiency and simplifying the panel process, the first reflective layer **103** and the second gate **421** are disposed on a same layer, or the second gate **421** is multiplexed as the first reflective layer **103**, and the material of the first reflective layer **103** may be same as the material of the second gate **421**. In some embodiments, the material of the first reflective layer **103** may be different from the material of the second gate **421**.

[0056] Referring to FIG. 10, FIG. 10 is a partial schematic view of a display panel according to another embodiment of the present application. In the figure, the display panel **10** includes a first metal layer **11**, and the first metal layer **11** is located on a side of any one of the first source **413**, the first drain **414**, the second source **423**, or the second drain **424** facing away from the base substrate **100**, where the first reflective layer **103** is located on the first metal layer **11**.

[0057] In this case, the display panel may include a first planarization layer **501** and a second planarization layer **502** located on a side of any one of the first source **413**, the first drain **414**, the second source **423**, or the second drain **424** facing away from the base substrate **100**. The first

metal layer **11** is at least located on a side of the first planarization layer **501** facing away from the base substrate **100**. Part of wires on the first metal layer **11** may be connected to the first voltage signal line **301** in parallel so that a voltage drop on the first voltage signal line **301** is reduced. In one embodiment, the first voltage signal line **301** may be located on the first metal layer **11**, since the first metal layer **11** has fewer wires, the first voltage signal line **301** may be set to be relatively wide so that the voltage drop thereon is reduced. The first reflective layer **103** is located on the first metal layer **11**, and since the first reflective layer **103** is located on a side of any one of the first source **413**, the first drain **414**, the second source **423**, or the second drain **424** facing away from the base substrate **100**, the first reflective layer **103** is relatively closer to the light-emitting element **200**, therefore the light efficiency loss is less, which is conducive to improve the light-emitting efficiency.

[0058] Referring to FIG. **11**, FIG. **11** is a partial schematic view of a display panel according to another embodiment of the present application. The display panel **10** includes a second metal layer **12**, the second metal layer **12** is located on a same layer as the first source **413** and/or the first drain **414**, or the second metal layer **12** is located on a same layer as the second source **423** and/or the second drain **424**, where the first reflective layer **103** is located on the second metal layer **12**.

[0059] Referring to FIG. **12**, FIG. **12** is a partial schematic view of a display panel according to another embodiment of the present application. In the figure, at least one of the first source **413**, the first drain **414**, the second source **423**, or the second drain **424** includes a first region **001**, the first region **001** extends and overlaps the light-emitting element **200**, and the first region **001** is multiplexed as the first reflective layer **103**.

[0060] In the preceding two cases, the first reflective layer **103** is disposed on the same layer as at least one of the first source **413**, the first drain **414**, the second source **423**, or the second drain **424**, or a first region of **001** of at least one of the first source **413**, the first drain **414**, the second source **423**, or the second drain **424** is multiplexed as the first reflective layer **103**. Generally speaking, as the source and the drain are located on a side of an entire structure of the transistor facing away from the base substrate, the source and the drain are relatively closer to the light-emitting element **200**, the first reflective layer **103** is disposed on this layer, so that a process for the first reflective layer **103** can be completed at a same layer with the manufacturing of the source and the drain, so that the process is simplified. In addition, as the first reflective layer **103** is relatively closer to the light-emitting element **200**, the light efficiency loss is reduced, which is conducive to improving the light-emitting efficiency. In particular, as shown in FIG. **12**, in a case where a first region **001** of the first drain **414** connected to the first extension part **1011** is multiplexed as the first reflective layer, the first extension part **1011** is also connected to the first reflective layer **103**, so that the problem of avoidance there between does not need to be considered, achieving a simple. It is to be noted that, in this case, at least part region of the second extension part **1022** does not overlap the first reflective layer **103**.

[0061] Referring to FIGS. **13** and **14**, FIG. **13** is a partial schematic view of a display panel according to another embodiment of the present application, and FIG. **14** is a partial schematic view of a display panel according to another embodiment of the present application. The first voltage signal line **301** and the second voltage signal line **302** are located on a side of at least one of the first electrode **101** or the second electrode **102** facing the base substrate **100**. As shown in FIG. **13**, the first reflective layer **103** is located on the same layer as at least one of the first voltage signal line **301** or the second voltage signal line **302**. In one embodiment, as shown in FIG. **14**, at least one of the first voltage signal line **301** or the second voltage signal line **302** is multiplexed as the first reflective layer **103**. FIG. **13** illustrates a case where the first reflective layer **103** and the second voltage signal line **302** are located on the same layer. In some other embodiments, the first reflective layer **103** may also be located on the same layer as the first voltage signal line **301**. In FIG. **14**, the first voltage signal line **301** is multiplexed as the first reflective layer **103**. In other embodiments, the second voltage signal line **302** may also be multiplexed as the first reflective

layer **103**. In conjunction with the preceding description, the first voltage signal line **301** and the second voltage signal line **302** may be located on the first metal layer **11** or on the second metal layer **12**. The first voltage signal line **301** and the second voltage signal line **302** may be located on a same layer or on different layers. For example, the first voltage signal line **301** is located on the first metal layer **11**, the second voltage signal line **302** is located on the second metal layer **12**; or the first voltage signal line **301** is located on the second metal layer **12**, and the second voltage signal line **302** is located on the first metal layer **11**.

[0062] Since the first voltage signal line **301** and the second voltage signal line **302** need to provide signals for the first electrode **101** and the second electrode **102**, the first voltage signal line **301** and the second voltage signal line **302** are generally set to be relatively closer to the light-emitting element **200**, and the first reflective layer **103** is disposed on a same layer as at least one of the first voltage signal line **301** or the second voltage signal line **302**. In such a way, the manufacturing of the first reflective layer **103** and at least one of the first voltage signal line **301** or the second voltage signal line **302** can be completed through a same mask, and thus the process is simplified while the light-emitting efficiency of the panel is ensured. In addition, the first voltage signal line **301** and the second voltage signal line **302** are generally connected to the drive elements in the panel. Generally, the signals on the first voltage signal and the second voltage signal need to be accurate. However, after the drive elements extending to the inside of the panel, when the first voltage signal line **301** and the second voltage signal line **302** is far away from the drive elements, the voltage drops on the first voltage signal line **301** and the second voltage signal line **302** are more significant. Therefore, to avoid the voltage drop, the width of the first voltage signal line **301** and the width of the second voltage signal line **302** are generally set to be relatively wider so that the voltage drop is reduced. In this case, relying on the relatively wide first voltage signal line **301** or second voltage signal line **302** being set to be relatively wider, at least one of the first voltage signal line **301** or the second voltage signal line **302** is multiplexed as the first reflective layer **103**. In such a way, on the one hand, a relatively small voltage drops on the first voltage signal line **301** or the second voltage signal line **302** is ensured; and on the other hand, an existing structure of the panel is fully utilized as the first reflective layer **103** so that the process is simplified, and the cost is saved.

[0063] Referring to FIGS. **14** and **15**, FIG. **15** is a partial schematic view of a display panel according to another embodiment of the present application. As shown in FIG. **15**, the first voltage signal line **301** is located on a side of the second voltage signal line **302** facing away from the base substrate **100**; or as shown in FIG. **14**, the first voltage signal line **301** and the second voltage signal line **302** are located on a same layer, where at least the first voltage signal line **301** is multiplexed as the first reflective layer **103**.

[0064] Referring to FIG. **15**, the width **W1** of the first voltage signal line **301** is greater than the width **W2** of the second voltage signal line **302**, where the first voltage signal line **301** is multiplexed as the first reflective layer **103**. It is to be noted herein that the width **W1** and the width **W2** generally refer to a width in directions perpendicular to the extension directions of corresponding voltage signal lines and parallel to the plane where the base substrate **100** is located. The first voltage signal line **301** and the second voltage signal line **302** may extend in a same direction or may extend in different directions.

[0065] The first voltage signal line **301** is configured to provide the first voltage signal for the pixel circuit **400**, and the first voltage signal is a high voltage signal, which is a crucial factor in a calculation formula of the drive current received by the light-emitting element **200**. To ensure that the drive current is as accurate as possible, the first voltage signal needs to be as accurate as possible. Therefore, generally, the first voltage signal line **301** may be set to be relatively wider in the panel, and the first voltage signal line **301** may be disposed on the first metal layer **11**. Since the first metal layer **11** is on a side of the film layers of the transistors facing away from the base substrate and the first metal layer **11** has fewer wires, the first voltage signal line **301** may be set to

be relatively wider. In conjunction with these aspects, at least the first voltage signal line is multiplexed as the first reflective layer **103** so that the panel structure is simplified, and the light-emitting efficiency of the panel is ensured.

[0066] Referring to FIG. **16**, FIG. **16** is a partial schematic view of a display panel according to another embodiment of the present application. In the figure, the first voltage signal line **301** is multiplexed as the first reflective layer **103** corresponding to at least one light-emitting element **200**, and the second voltage signal line **302** is multiplexed as the first reflective layer **103** corresponding to at least one light-emitting element **200**. In a case where a special case exists in the panel, the width of the first voltage signal line **301** is limited, and the case where the first voltage signal line **301** is multiplexed as the first reflective layer **103** corresponding to all the light-emitting elements **200** is limited; it is also feasible that the first voltage signal line **301** is multiplexed as the first reflective layer **103** corresponding to part of the light-emitting elements **200**, and the second voltage signal line **302** is multiplexed as the first reflective layer **103** corresponding to part of the light-emitting elements **200**.

[0067] Referring to FIGS. **14** to **16**, in this embodiment, in the case where the first voltage signal line **301** is multiplexed as the first reflective layer **103**, the second extension part **1022** does not overlap the first reflective layer **103**; or in the case where the second voltage signal line **302** is multiplexed as the first reflective layer **103**, the first extension part **1011** and the first reflective layer **103** do not overlap. For example, in the case where the first voltage signal line **301** is multiplexed as the first reflective layer **103**, the second extension part **1022** needs to be connected to the second voltage signal line **302**. To ensure that the connection is unimpeded, the second extension part **1022** does not overlap the first reflective layer **103**. In the case where the second voltage signal line **302** is multiplexed as the first reflective layer **103**, the first extension part **1011** needs to be connected to the first voltage signal line **301**. To ensure that the connection is unimpeded, the first extension part **1011** and the first reflective layers **103** do not overlap.

[0068] Referring to FIG. **17**, FIG. **17** is a partial schematic view of a display panel according to another embodiment of the present application. The first reflective layer **103** is connected to the first voltage signal line **301** in parallel so that the first voltage signal is received, or the first reflective layer **103** is connected to the second voltage signal line **302** in parallel so that the second voltage signal is received. FIG. **17** illustrates a case where the first reflective layer **103** is connected to the first voltage signal line **301** in parallel. In other embodiments, the first reflective layer **103** may be connected to the second voltage signal line **302** in parallel. As described above, the voltage drops on the first voltage signal line **301** and the second voltage signal line **302** need to be relatively small, hence the first reflective layer **103** may be connected to the first voltage signal line **301** or to the second voltage signal line **302** in parallel so that the voltage drops on the first voltage signal line **301** and the second voltage signal line **302** are reduced.

[0069] With continued reference to FIG. **17**, the first reflective layer **103** is located on a side of both the first voltage signal line **301** and the second voltage signal line **302** facing away from the base substrate **100**. Since the first reflective layer **103** is relatively close to the light-emitting element **200**, the light loss therein is reduced, which is conducive to improving the light-emitting efficiency of the display panel. Therefore, in a case where the first reflective layer **103** is not located in a same layer as the first voltage signal line **301** or the second voltage signal line **302**, the first reflective layer **103** may be located on a side of the first voltage signal line **301** and the second voltage signal line **302** facing away from the base substrate **100** so that the light-emitting efficiency of the display panel is improved.

[0070] Referring to FIG. **18**, FIG. **18** is a top view of voltage signal lines according to an embodiment of the present application. First voltage signal lines **301** and second voltage signal lines **302** may extend in the same direction. In this case, a first voltage signal bus that introduces multiple first voltage signal lines **301** may be located on the same side of the display panel as a second voltage signal bus that introduces multiple second voltage signal lines **302**, and the first

voltage signal lines **301** and the second voltage signal lines **302** may be located on a same film layer. In other embodiments, the extension direction of each first voltage signal line **301** may be perpendicular to the extension direction of each second voltage signal line **302**. In this case, the first voltage signal line **301** and the second voltage signal line **302** may be located on different layers, and the first voltage signal line **301** is disposed on a side of the second voltage signal line **302** facing away from the base substrate so that the width of the first voltage signal line **301** may be set to be wider than the width of the second voltage signal line **302**. In other embodiments, the first voltage signal lines **301** may extend in one direction, and the second voltage signal lines **302** may extend in two directions to form a grid structure, where part of the second voltage signal lines **302** are parallel to the first voltage signal lines **301**, and another part of the second voltage signal lines **302** are perpendicular to the first voltage signal lines **301**. In other embodiments, it is also feasible that the first voltage signal lines **301** may extend in two directions, and the second voltage signal lines **302** may extend in one direction, where part of the first voltage signal lines **301** are parallel to the second voltage signal lines **302**, and part of the first voltage signal lines **301** are perpendicular to the second voltage signal lines **302**. The specific structures depend on specific cases, which is not limited in this embodiment.

[0071] Referring to FIG. **19**, FIG. **19** is a partial schematic view of a display panel according to another embodiment of the present application. In the figure, the first electrode **101** and the second electrode **102** are both located on a side of the light-emitting element **200** facing the base substrate **100**, at least one of the first electrode **101** or the second electrode **102** is multiplexed as the first reflective layer **103**, and the extension part of the one of the first electrode **101** or the second electrode **102** multiplexed as the first reflective layer **103** does not overlap the extension part of the other one of the first electrode **101** or the second electrode **102**. FIG. **19** illustrates a case where the first electrode **101** is multiplexed as the first reflective layer **103**. In other embodiments, the second electrode **102** may be multiplexed as the first reflective layer **103**.

[0072] The first electrode **101** or the second electrode **102** is multiplexed as the first reflective layer **103**. In such a way, on the one hand, the first electrode **101** and the second electrode **102** are very close to the light-emitting element **200**, and the multiplex herein would cause the light loss between the light-emitting element **200** and the first reflective layers **103** to be relatively less, so that the light-emitting efficiency of the display panel is improved; and meanwhile, an additional film layer does not need to be provided as the first reflective layer **103** so that the panel process is simplified. It is to be noted that to ensure the fully reflection effect of the first reflective layer **103**, the area of the first reflective layer **103** is generally greater than the area of the light-emitting element **200**. Therefore, generally speaking, one of the first electrode **101** or the second electrode **102** closer to a side of the base substrate **100** is multiplexed as the first reflective layer **103** so that both the first electrode **101** and the second electrode **102** may be connected to the light-emitting element **200**, and the reflection effect of the first reflective layer **103** is ensured. FIG. **19** illustrates a case where the first electrode **101** is located on a side of the second electrode **102** facing the base substrate **100** and is multiplexed as the first reflective layer **103**. In other embodiments, the second electrode **102** is located on a side of the first electrode **101** facing the base substrate **100** and is multiplexed as the first reflective layer.

[0073] Referring to FIGS. **19** and **20**, FIG. **20** is a schematic diagram of a light-emitting element according to an embodiment of the present disclosure. In an embodiment, the first electrode **101** is located on a side of the second electrode **102** facing the base substrate **100**, the first electrode **101** is multiplexed as the first reflective layer **103**, and the second extension part **1022** does not overlap the first reflective layer **103**. Since the first electrode **101** is connected to the

[0074] P-type region **601** of the light-emitting element **200**, and the second electrode **102** is connected to the N-type region **602** of the light-emitting element **200**; generally, a height of the P-type region **601** is greater than a height of the N-type region **602**, and a height difference between the P-type region and the N-type region exists. In this case, the first electrode **101** is arranged to be

located on a side of the second electrode **102** facing the base substrate, so that structural characteristics of the light-emitting element **200** are matched. The second extension part **1022** is located on a side of the first electrode **101** facing away from the base substrate, and to ensure a normal connection between the second extension part **1022** and the second voltage signal line **302**, the second extension part **1022** does not overlap the first reflective layer **103**.

[0075] Referring to FIGS. **21** and **22**, FIG. **21** is a schematic diagram of another light-emitting element according to an embodiment of the present disclosure, and FIG. **22** is a schematic diagram of another light-emitting element according to an embodiment of the present disclosure. As shown in FIG. **21**, the first reflective layer **103** is located on the same layer as at least one of the first electrode **101** or the second electrode **102**; or as shown in FIG. **22**, the first reflective layer **103** is located on the same layer as one of the first electrode **101** or the second electrode **102** closer to a side of the base substrate **100**. The first reflective layer **103** may be located on a same layer as the first electrode **101** or the second electrode **102**, and the reflective layer **103** may not be electrically connected to the first electrode **101** or the second electrode **102**. In such an arrangement, since the first reflective layer **103** is relatively closer to the light-emitting element **200**, the light-emitting efficiency can be ensured; in addition, the first reflective layer **103** is prepared by a same process as the first electrode **101** or the second electrode **102**, so that the process is fully simplified, and the panel structure is simplified.

[0076] Referring to FIGS. **23** and **24**, FIG. **23** is a partial top view of a display panel according to another embodiment of the present disclosure, and FIG. **24** is a partial top view of a display panel according to another embodiment of the present disclosure. The first reflective layer **103** extends along a first direction X, and the first extension part **1011** and/or the second extension part **1022** extend along a second direction Y, where the first direction X and the second direction Y are perpendicular to each other and are both parallel to the plane where the base substrate **100** is located. As shown in FIG. **23**, the first extension part **1011** and the second extension part **1022** are located on a same side surface of the light-emitting element **200**, while as shown in FIG. **24**, the first extension part **1011** and the second extension part **1022** are located on opposite sides of the light-emitting element **200**. In such an arrangement, the extension directions of the first extension part **1011** and the extension directions of the second extension part **1022** may be staggered with the extension direction of the first reflective layer **103**, which is conducive to the electrical connection between the first extension part **1011** and a respective voltage signal line and to the electrical connection between the electrical connection between the second extension part **1022** and a respective voltage signal line.

[0077] It is to be noted that, what is shown in both FIGS. **23** and **24** is that, the first reflective layers **103** corresponding to the light-emitting elements **200** in a same column are all connected together, to simplifying a structure of the mask. However, in some special cases, different light-emitting elements **200** in the same column may also be disconnected from each other so that other designs may be made in gaps between adjacent light-emitting elements **200**, and thus the influence on the first reflective layer **103** is avoided.

[0078] Referring to FIG. **25**, FIG. **25** is a partial schematic view of a display panel according to another embodiment of the present application. The display panel **10** further includes a barrier layer **700** and a second reflective layer **104**. The barrier layer **700** is located between adjacent light-emitting elements **200**. The second reflective layer **104** is located on a side of the barrier layer **700** facing away from the base substrate **100**, and at least part of the second reflective layer **104** is located on a side wall of the barrier layer **700** facing the light-emitting element **200**. It is to be noted that the barrier layer **700** here is a structure that is disposed between adjacent light-emitting elements **700** to block light crosstalk between adjacent light-emitting elements **700**, and a color of the barrier layer **700** may be transparent or black. A material of the second reflective layer **104** may be a metal material such as silver, aluminum, titanium, or molybdenum, or an alloy material containing silver, aluminum, titanium, or molybdenum, or the material of the second reflective

layer **104** may be a fluorescent material with a reflective property.

[0079] As light emitted by the light-emitting element **200** is emitted in various directions, and is emitted not only to the backlight side, but also to a surrounding region in the lateral direction, leading to the light loss. In this embodiment, the second reflective layer **104** is disposed on the side wall of the barrier layer **700**, so that the light emitted by the light-emitting element **200** to the surrounding region may be reflected toward the light-emitting side, the side light is fully utilized, and the light-emitting efficiency is further improved.

[0080] In an embodiment, as shown in FIG. **25**, the second reflective layer **104** is electrically connected to the first electrode **101**, or the second reflective layer **104** is electrically connected to the second electrode **102**. In FIG. **25**, the second reflective layer **104** is electrically connected to the first electrode **101**. In other embodiments, the second reflective layer **104** may also be electrically connected to the second electrode **102**. Since the second reflective layer is disposed above the barrier layer **700**, in a case where the second metal layer is a conductive material such as a metal material and is separately disposed in the air, since the second metal layer is relatively close to the light-emitting element **200**, more static electricity may gather on the second reflective layer as time goes by, and the accumulation of the static electricity may cause damage to the light-emitting element **200**. Therefore, in this embodiment, the second reflective layer **104** may be electrically connected to the first electrode **101** that is applied with a high voltage signal or the second electrode **102** that is applied with a low voltage signal so that the second reflective layer **104** may be maintained at a same potential as the first electrode **101** or the second electrode **102**, and thus the static electricity is prevented from being accumulated on the second reflective layer **104** and affecting the display effect.

[0081] As shown in FIG. **25**, in an embodiment, the second reflective layer **104** extends along the side wall of the barrier layer **700** to contact the first electrode **101** or the second electrode **102**, and to electrically connect to the first electrode **101** or the second electrode **102**. FIG. **25** exemplarily illustrates a case where the second reflective layer **104** is in direct contact with the first electrode **101**. Since at least part region of the first reflective layer **104** is disposed on the side wall of the barrier layer **700**, the first reflective layer **104** is directly connected to the first electrode **101** after being extended so that the process is simplified, and the structure is simple.

[0082] With continued reference to FIG. **25**, in an embodiment, the barrier layer **700** may further include a first groove **701**. With the direction perpendicular to the base substrate **100** as the projection direction, the first groove **701** overlaps the first electrode **101** or the second electrode **102**, and the second reflective layer **104** extends into the first groove **701** and is electrically connected to the first electrode **101** or the second electrode **102**. In some cases, in a case where the second reflective layer **104** directly extends along the side wall of the barrier layer **700** to be connected to the first electrode **101** or the second electrode **102**, the following problem may exist: after the second reflective layer **104** contacts the first electrode **101**, a distance between the second reflective layer **104** and the second electrode **102** is too close, and the second reflective layer **104** short-circuits the first electrode **101** and the second electrode **102**. To avoid this problem, the first groove **701** is disposed on the barrier layer **700**, and the second reflective layer **104** is connected to the first electrode **101** or the second electrode **102** through the first groove **701**, so that the problem that the distance between the second reflective layer **104** and the other electrode is relatively close, and two electrodes are short-circuited is avoided.

[0083] Referring to FIG. **26**, FIG. **26** is a partial schematic view of a display panel according to another embodiment of the present application. The first electrode **101** extends to the side wall of the barrier layer **700** facing the light-emitting element **200** and is multiplexed as the second reflective layer **104**, and/or the second electrode **102** extends to the side wall of the barrier layer **700** facing the light-emitting element **200** and is multiplexed as the second reflective layer **104**. FIG. **26** illustrates a case where both the first electrode **101** and the second electrode **102** are multiplexed as the second reflective layer **104**. In other embodiments, only one of the first

electrode **101** or the second electrode **102** may be arranged to be multiplexed as the second reflective layer **104**. As described above, in a case where the second reflective layer **104** is a conductive material, the second reflective layer **104** needs to be electrically connected to the first electrode **101** or the second electrode **102**, so that the second reflective layer **104** is prevented from floating in the air. From the perspective of simplifying the process, the first electrode **101** or the second electrode **102** may be multiplexed as the second reflective layer **104**. In such a way, the second reflective layer **104** is formed while the first electrode **101** or the second electrode **102** is manufactured, so that the panel structure is fully simplified while the light-emitting efficiency is improved.

[0084] Referring to FIG. 27, FIG. 27 is a partial schematic view of a display panel according to another embodiment of the present application. In the figure, the first electrode **101** and the second electrode **102** are both located on a side of the light-emitting element **200** facing away from the base substrate **100**, the first electrode **101** is connected to the pixel circuit **400** through a first connection electrode **1111**, and the second electrode **102** is connected to the second voltage signal line **302** through a second connection electrode **1122**, where at least one of the first connection electrode **1111** or the second connection electrode **1122** is multiplexed as the second reflective layer **104**. In a case where the first electrode **101** and the second electrode **102** are both located on a side of the light-emitting element **200** facing away from the base substrate **100**, to ensure that the first electrode **101** and the second electrode **102** are connected to respective voltage signal lines, the first connection electrode **1111** and the second connection electrode **1122** may be arranged to extend from a side of the light-emitting element **200** facing away from the base substrate to a side of the light-emitting element **200** facing the base substrate. Based on this, the first connection electrode **1111** and the second connection electrode **1122** are generally conductive materials. Therefore, at least one of the first connection electrode **1111** or the second connection electrode **1122** may be multiplexed as the second reflective layer **104**, so that the second reflective layer **104** is formed by using the existing structure, and the panel process is fully simplified.

[0085] Referring to FIG. 28, FIG. 28 is a partial top view of a display panel according to another embodiment of the present disclosure. In the figure, the second reflective layer **104** is disposed around the light-emitting element **200**, the first extension part **1011** and the second extension part **1022** extend along the second direction Y, and at least one of two side surfaces of the light-emitting element **200** arranged along the second direction Y is not provided with the second reflective layer **104**.

[0086] This design is mainly because the second reflective layer **104** is generally connected to one of the first electrode **101** or the second electrode **102**. In a case where the second reflective layer **104** is connected to one of the first electrode **101** or the second electrode **102**, the second reflective layer **104** is not allowed to be connected to the other one of the first electrode **101** or the second electrode **102**, otherwise the first electrode **101** and the second electrode **102** are short-circuited. In order to connect to the voltage signal lines, the first extension part **1011** and the second extension part **1022** are generally designed to be relatively longer. For example, in a case where the first electrode **101** and the second reflective layer **104** are connected, and the second reflective layer **104** is close to the second extension part **1022**, short circuit is easy to occur. Therefore, in the present application, at least one of the two side surfaces of the light-emitting element **200** arranged along the second direction Y is not provided with the second reflective layer **104**, so that the following problem is avoided: an extension part of one electrode that is not connected to the second reflective layer **104** contacts the second reflective layer, and short circuit between the first electrode **101** and the second electrode **102** occurs.

[0087] With continued reference to FIG. 28, the two side surfaces of the light-emitting element **200** arranged along the second direction Y include a first side surface **211**, the first extension part **1011** and the second extension part **1022** are both located on the first side surface **211**, and the first side surface is not provided with the second reflective layer **104**. In this case, on the one hand, the first

extension part **1011** and the second extension part **1022** are located on a same side of the light-emitting element, which is conducive to a rational space utilization of the panel and improve the resolution of the panel. On the other hand, as described above, the first side surface is not provided with the second reflective layer so that the following case is avoided: an extension part of one electrode that is not connected to the second reflective layer **104** contacts the second reflective layer **104**, and short circuit between the first electrode **101** and the second electrode **102** occurs. [0088] Referring to FIGS. **29** and **30**, FIG. **29** is a partial schematic view of a display panel according to another embodiment of the present application, and FIG. **30** is a partial schematic view of a display panel according to another embodiment of the present application. The display panel **10** further includes a third reflective layer **105**, the third reflective layer **105** is located between at least one of the first electrode **101** or the second electrode **102** and the first reflective layer **103**, and the third reflective layer **105** is at least partially disposed around the first reflective layer **103**.

[0089] Further, as shown in FIG. **30**, along the direction perpendicular to the base substrate **100**, a height of the third reflective layer **105** is greater than a height of the first reflective layer **103**.

[0090] In the preceding design, the following is mainly considered: the first reflective layer **103** is located below the light-emitting element **200**; after the light emitted obliquely downward from the light-emitting element **200** is reflected by the first reflective layer **103**, the light is reflected to the upper right and is possibly emitted in a non-luminous region between adjacent light-emitting elements **200** according to the reflection principle, causing a problem of color mixing. To avoid this problem, the third reflective layer **105** is set to have a height greater than the height of the first reflective layer **103**, and is set to be disposed around the first reflective layer. In such a way, the light emitted obliquely downward from the light-emitting element **200** may be reflected again to the light-emitting side corresponding to the light-emitting element **200**, so that the light-emitting effect of the display panel is further improved, and the phenomenon of color mixing of the display panel is avoided.

[0091] Another aspect of embodiments of the present application provides a display device. Referring to FIG. **31**, FIG. **31** is a schematic diagram of a display device according to an embodiment of the present application. A display device **20** includes the display panel **10**, and the display panel **10** includes all display panels described in the preceding embodiments. The display device **20** may be one of a variety of display devices such as a TV, a notebook, a mobile phone, and a smart wearable display device, which is not limited in this embodiment.

[0092] In the preceding description, embodiments of the present application provide the display panel **10** and the display device **20**. The display panel **10** includes the first electrode **101** and the second electrode **102**, and the first electrode **101** and the second electrode **102** are both located on the same side of the light-emitting element **200** relative to the base substrate **100**; the display panel **10** includes the first reflective layer **103**, the first reflective layer **103** is located on a side of the light-emitting element **200** facing the base substrate **100**, that is, on the backlight side, and the first reflective layer **103** covers the light-emitting element **200** so that the light emitted by the light-emitting element **200** to the backlight side may be reflected toward the light-emitting side, and thus the light-emitting efficiency of the display panel is improved. Based on this structure, the display panel **10** further includes the voltage signal line **300** located on a side of the light-emitting element **200** facing the base substrate; the first electrode **101** further includes the first extension part **1011**, and the second electrode **102** further includes the second extension part **1022**; the first extension part **1011** and the second extension part **1022** are connected to the voltage signal line **300**; the first electrode **101** and the second electrode **102** need to receive voltage signals from one side of the base substrate **100** and provide the voltage signals for the light-emitting element **200**, and the first reflective layer **103** covers the light-emitting element **200**. Therefore, to ensure the normal operation of the first electrode **101** and the second electrode **102**, the first extension part **1011** and the second extension part **1022** need to be provided, and at least one of the first extension part **1011**

or the second extension part **1022** does not overlap the first reflective layer **103** so that it is ensured that the first electrode **101** and the second electrode **102** normally receive the voltage signals, and the light-emitting efficiency of the display panel is improved.

Claims

1. A display panel, comprising: a base substrate; a light-emitting element, wherein the light-emitting element is located on a side of the base substrate; a first electrode and a second electrode, wherein the first electrode and the second electrode are electrically connected to the light-emitting element, and are both located on a side of the light-emitting element facing the base substrate or both located on a side of the light-emitting element facing away from the base substrate; a first reflective layer, wherein the first reflective layer is located on a side of the light-emitting element facing the base substrate, and with a direction perpendicular to the base substrate as a projection direction, the first reflective layer at least partially covers the light-emitting element; and a pixel circuit, wherein the pixel circuit is electrically connected to the light-emitting element, and the pixel circuit comprises a first transistor and a second transistor; and wherein with the direction perpendicular to the base substrate as the projection direction, at least one of the first transistor or the second transistor does not overlap the first reflective layer.
2. The display panel of claim 1, wherein with the direction perpendicular to the base substrate as the projection direction, at least one of the first transistor or the second transistor does not overlap the light-emitting element.
3. The display panel of claim 1, wherein at least one of the first electrode or the second electrode is also served as the first reflective layer; or wherein the first reflective layer is located on a same layer as at least one of the first electrode or the second electrode; or wherein the display panel further comprises a voltage signal line, the voltage signal line comprises a first voltage signal line that provides a first voltage signal and a second voltage signal line that provides a second voltage signal, and a voltage of the first voltage signal is higher than a voltage of the second voltage signal; and wherein the first reflective layer is located on a same layer as at least one of the first voltage signal line or the second voltage signal line, or, at least one of the first voltage signal line or the second voltage signal line is also served as the first reflective layer.
4. The display panel of claim 3, wherein the voltage signal line is located on a side of the light-emitting element facing the base substrate, and wherein the first electrode comprises a first extension part, the second electrode comprises a second extension part, at least one of the first extension part or the second extension part is connected to the voltage signal line, and with the direction perpendicular to the base substrate as the projection direction, at least one of the first extension part or the second extension part does not overlap the first reflective layer.
5. The display panel of claim 3, wherein the pixel circuit is connected to the first voltage signal line, and the first extension part receives the first voltage signal through transistors of the pixel circuit; and wherein the second extension part is connected to the second voltage signal line and is configured to receive the second voltage signal.
6. The display panel of claim 4, wherein at least the first extension part does not overlap the first reflective layer.
7. The display panel of claim 4, wherein a length of the first extension part is greater than a length of the second extension part.
8. The display panel of claim 3, wherein the first transistor comprises a first gate, a first active layer, a first source, and a first drain, and the second transistor comprises a second gate, a second active layer, a second source, and a second drain, and wherein the first extension part is connected to the first drain, and at least part of a structure of the first transistor is located on a side of the first reflective layer facing the base substrate.
9. The display panel of claim 8, wherein the first reflective layer is located on a side of both the

first gate and the second gate facing away from the base substrate.

10. The display panel of claim 8, wherein the display panel comprises a first metal layer, wherein the first metal layer is located on a side of any one of the first source, the first drain, the second source, or the second drain facing away from the base substrate, and wherein the first reflective layer is located on the first metal layer.

11. The display panel of claim 3, wherein a width of the first voltage signal line is greater than a width of the second voltage signal line.

12. The display panel of claim 3, wherein the first voltage signal line and the second voltage signal line are located on a side of at least one of the first electrode or the second electrode facing the base substrate.

13. The display panel of claim 12, wherein the first voltage signal line is located on a side of the second voltage signal line facing away from the base substrate, or the first voltage signal line and the second voltage signal line are located on a same layer.

14. The display panel of claim 3, wherein the first reflective layer is connected to the first voltage signal line in parallel and receives the first voltage signal, or the first reflective layer is connected to the second voltage signal line in parallel and receives the second voltage signal.

15. The display panel of claim 4, wherein in a case where the first voltage signal line is also served as the first reflective layer, the second extension part does not overlap the first reflective layer; or in a case where the second voltage signal line is also served as the first reflective layer, the first extension part does not overlap the first reflective layer.

16. The display panel of claim 3, wherein the first reflective layer is located on a side of both the first voltage signal line and the second voltage signal line facing away from the base substrate.

17. The display panel of claim 3, wherein an extension part of one of the first electrode and the second electrode that is also served as the first reflective layer and an extension part of the other one of the first electrode or the second electrode do not overlap.

18. The display panel of claim 3, wherein the first electrode is located on a side of the second electrode facing the base substrate; and wherein the first electrode is also served as the first reflective layer, and the second extension part does not overlap the first reflective layer.

19. The display panel of claim 3, wherein the first reflective layer is located on a same layer as one of the first electrode or the second electrode closer to a side of the base substrate.

20. A display device, comprising a display panel, wherein the display panel comprising: a base substrate; a light-emitting element, wherein the light-emitting element is located on a side of the base substrate; a first electrode and a second electrode, wherein the first electrode and the second electrode are electrically connected to the light-emitting element, and are both located on a side of the light-emitting element facing the base substrate or both located on a side of the light-emitting element facing away from the base substrate; a first reflective layer, wherein the first reflective layer is located on a side of the light-emitting element facing the base substrate, and with a direction perpendicular to the base substrate as a projection direction, the first reflective layer at least partially covers the light-emitting element; and a pixel circuit, wherein the pixel circuit is electrically connected to the light-emitting element, and the pixel circuit comprises a first transistor and a second transistor; and wherein with the direction perpendicular to the base substrate as the projection direction, at least one of the first transistor or the second transistor does not overlap the first reflective layer.
