

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287377

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

MAAMARI; Diana et al.

FREQUENCY RESOURCE SELECTION FOR MULTIPLE CHANNELS

Abstract

Methods, systems, and devices for wireless communication are described. In some systems, a network entity may transmit, to a user equipment (UE), scheduling information that allocates multiple uplink channels of a same channel type to the UE. The scheduling information may indicate respective sets of frequency resources for each of the uplink channels. The network entity may transmit an indication that uplink channel selection by the UE is enabled. The UE may select a first uplink channel from the multiple uplink channels allocated by the scheduling information based on the indication that uplink shared channel selection is enabled. The UE may transmit an uplink message via the first uplink channel, and the UE may refrain from transmitting via other uplink channels of the multiple uplink channels allocated by the scheduling information based on selecting the first uplink channel.

Inventors: MAAMARI; Diana (San Diego, CA), ELSHAFIE; Ahmed (San Diego, CA), XU; Huilin (Temecula, CA), HANDE; Prashanth Haridas (San Diego, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 89664152

Appl. No.: 19/214764

Filed: May 21, 2025

Related U.S. Application Data

parent US continuation 17877162 20220729 parent-grant-document US 12323972 child US 19214764

Publication Classification

Int. Cl.: H04W72/1268 (20230101); H04W72/0453 (20230101)

Background/Summary

CROSS REFERENCE [0001] The present Application for Patent is a continuation of U.S. patent application Ser. No. 17/877,162 by MAAMARI et al., entitled “FREQUENCY RESOURCE SELECTION FOR MULTIPLE CHANNELS” and filed Jul. 29, 2022, which is assigned to the assignee hereof and is expressly incorporated by reference in its entirety herein.

FIELD OF TECHNOLOGY

[0002] The following relates to wireless communication, including frequency resource selection for multiple channels.

BACKGROUND

[0003] Wireless communications systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). Examples of such multiple-access systems include fourth generation (4G) systems such as Long-Term Evolution (LTE) systems, LTE-Advanced (LTE-A) systems, or LTE-A Pro systems, and fifth generation (5G) systems which may be referred to as New Radio (NR) systems. These systems may employ technologies such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal FDMA (OFDMA), or discrete Fourier transform spread orthogonal frequency division multiplexing (DFT-S-OFDM). A wireless multiple-access communications system may include one or more base stations, each supporting wireless communication for communication devices, which may be known as user equipment (UE).

[0004] In some systems, a network entity may transmit scheduling information via a dynamic grant or one or more configured grants. The scheduling information may allocate channel resources for one or more uplink or downlink channels.

SUMMARY

[0005] The described techniques relate to improved methods, systems, devices, and apparatuses that support frequency resource selection for multiple channels. For example, the described techniques provide for a network to schedule multiple channels having different frequency resource allocations and for a user equipment (UE) to select at least one channel from among the multiple allocated channels. The UE may receive scheduling information that allocates the multiple channels having a same channel type. The channel type may be uplink, downlink, shared channel, control channel, or any combination thereof. In some aspects, the scheduling information may allocate a respective set of frequency sources within each of the multiple channels. Allocation of multiple sets of overlapping or non-overlapping frequency resources may improve communication reliability due to frequency diversity among the allocated resources, for example.

[0006] If the scheduling information allocates multiple uplink channels, the network entity may transmit an indication that uplink channel selection by the UE is enabled for the multiple uplink channels. In such cases, the UE may select at least a first uplink channel from among the multiple uplink channels allocated via the scheduling information. The first uplink channel may be associated with or may include a first set of frequency resources. The UE may transmit an uplink message and an indication of the selection via the first uplink channel based on the selection. The UE may refrain from transmitting via at least a portion of one or more other uplink channels of the set of multiple uplink channels allocated via the scheduling information based on the selection. The

UE may thereby refrain from transmitting excessive information if uplink channel resources are overallocated, which may reduce processing, power consumption, and overhead.

[0007] A method for wireless communication at a UE is described. The method may include receiving scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels, selecting, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources, transmitting an uplink message via the first uplink channel based on the selecting, and refraining from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources.

[0008] An apparatus for wireless communication is described. The apparatus may include a memory, a transceiver, and at least one processor of a UE, the at least one processor coupled with the memory and the transceiver. The at least one processor may be configured to receive scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels, select, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources, transmit an uplink message via the first uplink channel based on the selecting, and refrain from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources.

[0009] Another apparatus for wireless communication at a UE is described. The apparatus may include means for receiving scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels, means for selecting, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources, means for transmitting an uplink message via the first uplink channel based on the selecting, and means for refraining from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources.

[0010] A non-transitory computer-readable medium storing code for wireless communication at a UE is described. The code may include instructions executable by a processor to receive scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels, select, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources, transmit an uplink message via the first uplink channel based on the selecting, and refrain from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources.

[0011] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, receiving the scheduling information may include operations, features, means, or instructions for receiving, via the scheduling information, an indication that uplink channel selection by the UE may be enabled for the set of multiple uplink channels, where the UE selecting the first uplink channel may be based on the indication that uplink channel selection is enabled.

[0012] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the scheduling information includes a downlink control information (DCI) message and the indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels may include a format of the DCI message.

[0013] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the set of multiple uplink channels may be at least partially overlapping

in a frequency domain and the method, apparatuses, and non-transitory computer-readable medium may include further operations, features, means, or instructions for transmitting, within a subset of the first set of frequency resources that may be common to the set of multiple uplink channels, uplink control information (UCI) that indicates that the UE may have selected the first uplink channel from among the set of multiple uplink channels.

[0014] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for selecting a second subset of the first set of frequency resources for transmitting the uplink message, where the uplink message may be transmitted within the second subset of the first set of frequency resources, and where the UCI further indicates that the UE may have selected the second subset for transmitting the uplink message.

[0015] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for receiving, via the scheduling information or a control message that may be different than the scheduling information, an indication of the subset of the first set of frequency resources that may be common to the set of multiple uplink channels.

[0016] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the set of multiple uplink channels may be at least partially overlapping in a frequency domain and the method, apparatuses, and non-transitory computer-readable medium may include further operations, features, means, or instructions for transmitting, via a subset of the first set of frequency resources, a demodulation reference signal (DMRS) sequence that indicates that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the subset of the first set of frequency resources may be common to the set of multiple uplink channels.

[0017] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, each of the set of multiple uplink channels includes a respective set of reserved resources for UCI and the method, apparatuses, and non-transitory computer-readable medium may include further operations, features, means, or instructions for transmitting, via the respective set of reserved resources within the first uplink channel, UCI that indicates that the UE may have selected the first uplink channel from among the set of multiple uplink channels.

[0018] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, each of the set of multiple uplink channels may be associated with a respective DMRS sequence and the method, apparatuses, and non-transitory computer-readable medium may include further operations, features, means, or instructions for transmitting, via a portion of the first uplink channel, the respective DMRS sequence for the first uplink channel to indicate that the UE has selected the first uplink channel from among the set of multiple uplink channels.

[0019] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, receiving the scheduling information may include operations, features, means, or instructions for receiving, within the scheduling information, a set of multiple frequency domain resource allocation (FDRA) fields that each allocate a respective uplink channel of the set of multiple uplink channels.

[0020] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for receiving a control message that indicates a set of multiple sets of frequency resources, where an FDRA field within the scheduling information indicates a subset of the set of multiple sets of frequency resources, the subset including the respective sets of frequency resources for the set of multiple uplink channels.

[0021] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, receiving the scheduling information may include operations, features,

means, or instructions for receiving a DCI message that allocates the set of multiple uplink channels to the UE and indicates the respective sets of frequency resources for the set of multiple uplink channels.

[0022] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, receiving the scheduling information may include operations, features, means, or instructions for receiving at least one configured grant that allocates the set of multiple uplink channels to the UE and indicates the respective sets of frequency resources for the set of multiple uplink channels.

[0023] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the set of multiple uplink channels allocated to the UE may be overlapping in a time domain and the set of multiple uplink channels allocated to the UE may be partially overlapping or non-overlapping in a frequency domain.

[0024] A method for wireless communication at a network entity is described. The method may include transmitting scheduling information that allocates a set of multiple uplink channels of a same channel type to a UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels, transmitting an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels, and receiving an uplink message via a first uplink channel based on identifying that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the first uplink channel includes a first set of frequency resources.

[0025] An apparatus for wireless communication is described. The apparatus may include a memory and at least one processor of a network entity, the at least one processor coupled with the memory. The at least one processor may be configured to transmit scheduling information that allocates a set of multiple uplink channels of a same channel type to a UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels, transmit an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels, and receive an uplink message via a first uplink channel based on identifying that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the first uplink channel includes a first set of frequency resources.

[0026] Another apparatus for wireless communication at a network entity is described. The apparatus may include means for transmitting scheduling information that allocates a set of multiple uplink channels of a same channel type to a UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels, means for transmitting an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels, and means for receiving an uplink message via a first uplink channel based on identifying that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the first uplink channel includes a first set of frequency resources.

[0027] A non-transitory computer-readable medium storing code for wireless communication at a network entity is described. The code may include instructions executable by a processor to transmit scheduling information that allocates a set of multiple uplink channels of a same channel type to a UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels, transmit an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels, and receive an uplink message via a first uplink channel based on identifying that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the first uplink channel includes a first set of frequency resources.

[0028] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, transmitting the scheduling information may include operations, features, means, or instructions for transmitting, within the scheduling information, the indication that uplink channel selection by the UE may be enabled for the set of multiple uplink channels.

[0029] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the set of multiple uplink channels may be at least partially overlapping in a frequency domain and the method, apparatuses, and non-transitory computer-readable medium may include further operations, features, means, or instructions for transmitting, via the scheduling information or a control message that may be different than the scheduling information, an indication of a subset of the first set of frequency resources that may be common to the set of multiple uplink channels and receiving, via the subset of the first set of frequency resources, an indication that the UE may have selected, from among the set of multiple uplink channels, at least a portion of the first set of frequency resources in the first uplink channel for transmitting the uplink message, where identifying that the UE selected the first uplink channel may be based on receiving the indication.

[0030] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, each of the set of multiple uplink channels includes a respective set of reserved resources for UCI and the method, apparatuses, and non-transitory computer-readable medium may include further operations, features, means, or instructions for receiving, via the respective set of reserved resources within the first uplink channel, UCI that indicates that the UE selected the first uplink channel from among the set of multiple uplink channels, where identifying that the UE may have selected the first uplink channel may be based on receiving the indication.

[0031] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, each of the set of multiple uplink channels may be associated with a respective DMRS sequence and the method, apparatuses, and non-transitory computer-readable medium may include further operations, features, means, or instructions for receiving, via a portion of the first uplink channel, the respective DMRS sequence for the first uplink channel, where identifying that the UE selected the first uplink channel may be based on receiving the respective DMRS sequence for the first uplink channel.

[0032] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, transmitting the scheduling information may include operations, features, means, or instructions for transmitting, within the scheduling information, a set of multiple FDRA fields that each allocate a respective uplink channel of the set of multiple uplink channels.

[0033] Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for transmitting a control message that indicates a set of multiple sets of frequency resources, where a FDRA field within the scheduling information indicates a subset of the set of multiple sets of frequency resources, the subset including the respective sets of frequency resources for the set of multiple uplink channels.

[0034] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, transmitting the scheduling information may include operations, features, means, or instructions for transmitting a DCI message or at least one configured grant that allocates the set of multiple uplink channels to the UE and indicates the respective sets of frequency resources for the set of multiple uplink channels.

[0035] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, no signaling may be received from the UE within at least a portion of a second uplink channel of the set of multiple uplink channels, the second uplink channel including a second set of frequency resources set.

[0036] In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the set of multiple uplink channels allocated to the UE may be overlapping in a time domain and the set of multiple uplink channels allocated to the UE may be partially overlapping or non-overlapping in a frequency domain.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0037] FIG. 1 illustrates an example of a wireless communications system that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0038] FIG. 2 illustrates an example of a wireless communications system that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0039] FIG. 3 illustrates an example of a channel configuration scheme that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0040] FIGS. 4-6 illustrate examples of uplink channel configurations that support frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0041] FIG. 7 illustrates an example of a process flow that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0042] FIGS. 8 and 9 show block diagrams of devices that support frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0043] FIG. 10 shows a block diagram of a communications manager that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0044] FIG. 11 shows a diagram of a system including a device that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0045] FIGS. 12 and 13 show block diagrams of devices that support frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0046] FIG. 14 shows a block diagram of a communications manager that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0047] FIG. 15 shows a diagram of a system including a device that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

[0048] FIGS. 16 through 20 show flowcharts illustrating methods that support frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure.

DETAILED DESCRIPTION

[0049] In some wireless communications systems, a network entity may transmit scheduling information that allocates multiple uplink or downlink channels of a same channel type (e.g., multiple physical uplink shared channels (PUSCHs), multiple physical downlink shared channels (PDSCHs), or multiple channels of some other type of channel. Each uplink or downlink channel may include or correspond to a set of channel resources that may be overlapping or non-overlapping in a time domain. For example, where multiple PUSCHs are allocated, the multiple PUSCHs may respectively correspond to multiple sets of PUSCH resources, with each allocated set of PUSCH resources referred to as an allocated PUSCH. As another example, where multiple PDSCHs are allocated, the multiple PDSCHs may respectively correspond to multiple sets of PDSCH resources, with each allocated set of PDSCH resources referred to as an allocated PDSCH. Thus, an allocated uplink channel may refer to an allocated set of uplink channel resources, and an allocated downlink channel may refer to an allocated set of downlink channel resources.

[0050] The scheduling information that allocates multiple uplink or downlink channels of a same channel type may be transmitted via a dynamic grant (e.g., via downlink control information (DCI)) or via one or more configured grants. The scheduling information may include a frequency

domain resource allocation (FDRA) field and a time domain resource allocation (TDRA) field for allocating the channel resources in the frequency domain and the time domain, respectively. In some cases, however, an FDRA field in a dynamic grant (e.g., DCI) may not support allocating different frequency resources to different uplink or downlink channels, which may reduce reliability of the scheduled communications due to lack of frequency diversity among the allocated resources, for example.

[0051] In some aspects, a user equipment (UE) may transmit a request for resources for transmissions by the UE, and a network entity may transmit scheduling information that allocates uplink channels for the UE based on the request. In some other aspects, the network entity may preschedule resources for transmissions by the UE without receiving a request from the UE, which may result in an overallocation of resources (e.g., as the network entity may allocate the resources without knowledge of how much uplink information may be in a buffer of the UE). In some systems, the UE may transmit within each set of resources allocated by the scheduling information even if the resources are overallocated (e.g., the amount of data in the buffer at the UE can be transmitted in fewer than all of the allocated resources), which may cause unnecessary signaling overhead and power consumption by the UE.

[0052] Techniques, systems, and devices described herein support allocation of multiple uplink or downlink channels having different frequency resource allocations (e.g., sets of resources that are non-overlapping or partially overlapping in a frequency domain). For example, a network entity may transmit scheduling information (e.g., a single DCI message, or one or more configured grants) to a UE that allocates multiple sets of uplink or downlink channel resources each associated with different frequency resource allocations. In some aspects, a single scheduling grant may include one or more FDRA fields configured to allocate multiple sets of frequency resources that are non-overlapping or partially overlapping in the frequency domain. The different frequency resource allocations may improve frequency diversity of transmissions, among other examples.

[0053] Additionally, or alternatively, techniques described herein support selection, by a UE and from among multiple uplink channels allocated by scheduling information, of at least a portion of an allocated uplink channel to utilize for uplink communications. For example, each uplink channel may be allocated a set of uplink channel resources, and the UE may select one or more of the sets of uplink channel resources, a subset of uplink channel resources from one or more of the sets, or both. The UE may refrain from transmitting within the uplink channel resources that were allocated by the scheduling information but not selected by the UE, which may reduce overhead and power consumption at the UE, among other examples. The UE may indicate the selected uplink channel resources to a network entity. In some aspects, the uplink channels allocated by the scheduling information may be at least partially overlapping in a time domain, a frequency domain, or both, and the overlapping portions may include resources common to each of the resource sets. The UE may transmit uplink control information (UCI) or a demodulation reference signal (DMRS) sequence via the common resources to indicate which set or subset of uplink channel resources the UE selected. Additionally, or alternatively, each uplink channel may include a respective set of reserved resources, and the UE may transmit UCI or a DMRS via the reserved resources of a given uplink channel to indicate that the UE selected that uplink channel.

[0054] Aspects of the disclosure are initially described in the context of wireless communications systems. Additional aspects are described with reference to channel configuration schemes, uplink channel configurations, and process flows. Aspects of the disclosure are further illustrated by and described with reference to apparatus diagrams, system diagrams, and flowcharts that relate to frequency resource selection for multiple channels.

[0055] FIG. 1 illustrates an example of a wireless communications system **100** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The wireless communications system **100** may include one or more network entities **105**, one or more UEs **115**, and a core network **130**. In some examples, the wireless

communications system **100** may be a Long-Term Evolution (LTE) network, an LTE-Advanced (LTE-A) network, an LTE-A Pro network, a New Radio (NR) network, or a network operating in accordance with other systems and radio technologies, including future systems and radio technologies not explicitly mentioned herein.

[0056] The network entities **105** may be dispersed throughout a geographic area to form the wireless communications system **100** and may include devices in different forms or having different capabilities. In various examples, a network entity **105** may be referred to as a network element, a mobility element, a radio access network (RAN) node, or network equipment, among other nomenclature. In some examples, network entities **105** and UEs **115** may wirelessly communicate via one or more communication links **125** (e.g., a radio frequency (RF) access link). For example, a network entity **105** may support a coverage area **110** (e.g., a geographic coverage area) over which the UEs **115** and the network entity **105** may establish one or more communication links **125**. The coverage area **110** may be an example of a geographic area over which a network entity **105** and a UE **115** may support the communication of signals according to one or more radio access technologies (RATs).

[0057] The UEs **115** may be dispersed throughout a coverage area **110** of the wireless communications system **100**, and each UE **115** may be stationary, or mobile, or both at different times. The UEs **115** may be devices in different forms or having different capabilities. Some example UEs **115** are illustrated in FIG. 1. The UEs **115** described herein may be capable of supporting communications with various types of devices, such as other UEs **115** or network entities **105**, as shown in FIG. 1.

[0058] As described herein, a node of the wireless communications system **100**, which may be referred to as a network node, or a wireless node, may be a network entity **105** (e.g., any network entity described herein), a UE **115** (e.g., any UE described herein), a network controller, an apparatus, a device, a computing system, one or more components, or another suitable processing entity configured to perform any of the techniques described herein. For example, a node may be a UE **115**. As another example, a node may be a network entity **105**. As another example, a first node may be configured to communicate with a second node or a third node. In one aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a UE **115**. In another aspect of this example, the first node may be a UE **115**, the second node may be a network entity **105**, and the third node may be a network entity **105**. In yet other aspects of this example, the first, second, and third nodes may be different relative to these examples. Similarly, reference to a UE **115**, network entity **105**, apparatus, device, computing system, or the like may include disclosure of the UE **115**, network entity **105**, apparatus, device, computing system, or the like being a node. For example, disclosure that a UE **115** is configured to receive information from a network entity **105** also discloses that a first node is configured to receive information from a second node.

[0059] In some examples, network entities **105** may communicate with the core network **130**, or with one another, or both. For example, network entities **105** may communicate with the core network **130** via one or more backhaul communication links **120** (e.g., in accordance with an S1, N2, N3, or other interface protocol). In some examples, network entities **105** may communicate with one another via a backhaul communication link **120** (e.g., in accordance with an X2, Xn, or other interface protocol) either directly (e.g., directly between network entities **105**) or indirectly (e.g., via a core network **130**). In some examples, network entities **105** may communicate with one another via a midhaul communication link **162** (e.g., in accordance with a midhaul interface protocol) or a fronthaul communication link **168** (e.g., in accordance with a fronthaul interface protocol), or any combination thereof. The backhaul communication links **120**, midhaul communication links **162**, or fronthaul communication links **168** may be or include one or more wired links (e.g., an electrical link, an optical fiber link), one or more wireless links (e.g., a radio link, a wireless optical link), among other examples or various combinations thereof. A UE **115**

may communicate with the core network **130** via a communication link **155**.

[0060] One or more of the network entities **105** described herein may include or may be referred to as a base station **140** (e.g., a base transceiver station, a radio base station, an NR base station, an access point, a radio transceiver, a NodeB, an eNodeB (eNB), a next-generation NodeB or a giga-NodeB (either of which may be referred to as a gNB), a 5G NB, a next-generation eNB (ng-eNB), a Home NodeB, a Home eNodeB, or other suitable terminology). In some examples, a network entity **105** (e.g., a base station **140**) may be implemented in an aggregated (e.g., monolithic, standalone) base station architecture, which may be configured to utilize a protocol stack that is physically or logically integrated within a single network entity **105** (e.g., a single RAN node, such as a base station **140**).

[0061] In some examples, a network entity **105** may be implemented in a disaggregated architecture (e.g., a disaggregated base station architecture, a disaggregated RAN architecture), which may be configured to utilize a protocol stack that is physically or logically distributed among two or more network entities **105**, such as an integrated access backhaul (IAB) network, an open RAN (O-RAN) (e.g., a network configuration sponsored by the O-RAN Alliance), or a virtualized RAN (vRAN) (e.g., a cloud RAN (C-RAN)). For example, a network entity **105** may include one or more of a central unit (CU) **160**, a distributed unit (DU) **165**, a radio unit (RU) **170**, a RAN Intelligent Controller (RIC) **175** (e.g., a Near-Real Time RIC (Near-RT RIC), a Non-Real Time RIC (Non-RT RIC)), a Service Management and Orchestration (SMO) **180** system, or any combination thereof. An RU **170** may also be referred to as a radio head, a smart radio head, a remote radio head (RRH), a remote radio unit (RRU), or a transmission reception point (TRP). One or more components of the network entities **105** in a disaggregated RAN architecture may be co-located, or one or more components of the network entities **105** may be located in distributed locations (e.g., separate physical locations). In some examples, one or more network entities **105** of a disaggregated RAN architecture may be implemented as virtual units (e.g., a virtual CU (VCU), a virtual DU (VDU), a virtual RU (VRU)).

[0062] The split of functionality between a CU **160**, a DU **165**, and an RU **170** is flexible and may support different functionalities depending upon which functions (e.g., network layer functions, protocol layer functions, baseband functions, RF functions, and any combinations thereof) are performed at a CU **160**, a DU **165**, or an RU **170**. For example, a functional split of a protocol stack may be employed between a CU **160** and a DU **165** such that the CU **160** may support one or more layers of the protocol stack and the DU **165** may support one or more different layers of the protocol stack. In some examples, the CU **160** may host upper protocol layer (e.g., layer 3 (L3), layer 2 (L2)) functionality and signaling (e.g., Radio Resource Control (RRC), service data adaptation protocol (SDAP), Packet Data Convergence Protocol (PDCP)). The CU **160** may be connected to one or more DUs **165** or RUs **170**, and the one or more DUs **165** or RUs **170** may host lower protocol layers, such as layer 1 (L1) (e.g., physical (PHY) layer) or L2 (e.g., radio link control (RLC) layer, medium access control (MAC) layer) functionality and signaling, and the one or more DUs **165** or RUs **170** may each be at least partially controlled by the CU **160**. Additionally, or alternatively, a functional split of the protocol stack may be employed between a DU **165** and an RU **170** such that the DU **165** may support one or more layers of the protocol stack and the RU **170** may support one or more different layers of the protocol stack. The DU **165** may support one or multiple different cells (e.g., via one or more RUs **170**). In some cases, a functional split between a CU **160** and a DU **165**, or between a DU **165** and an RU **170** may be within a protocol layer (e.g., some functions for a protocol layer may be performed by one of a CU **160**, a DU **165**, or an RU **170**, while other functions of the protocol layer are performed by a different one of the CU **160**, the DU **165**, or the RU **170**). A CU **160** may be functionally split further into CU control plane (CU-CP) and CU user plane (CU-UP) functions. A CU **160** may be connected to one or more DUs **165** via a midhaul communication link **162** (e.g., F1, F1-c, F1-u), and a DU **165** may be connected to one or more RUs **170** via a fronthaul communication link **168** (e.g., open fronthaul (FH) interface).

In some examples, a midhaul communication link **162** or a fronthaul communication link **168** may be implemented in accordance with an interface (e.g., a channel) between layers of a protocol stack supported by respective network entities **105** that are in communication via such communication links.

[0063] In wireless communications systems (e.g., wireless communications system **100**), infrastructure and spectral resources for radio access may support wireless backhaul link capabilities to supplement wired backhaul connections, providing an IAB network architecture (e.g., to a core network **130**). In some cases, in an IAB network, one or more network entities **105** (e.g., IAB nodes **104**) may be partially controlled by each other. One or more IAB nodes **104** may be referred to as a donor entity or an IAB donor. One or more DUs **165** or one or more RUs **170** may be partially controlled by one or more CUs **160** associated with a donor network entity **105** (e.g., a donor base station **140**). The one or more donor network entities **105** (e.g., IAB donors) may be in communication with one or more additional network entities **105** (e.g., IAB nodes **104**) via supported access and backhaul links (e.g., backhaul communication links **120**). IAB nodes **104** may include an IAB mobile termination (IAB-MT) controlled (e.g., scheduled) by DUs **165** of a coupled IAB donor. An IAB-MT may include an independent set of antennas for relay of communications with UEs **115**, or may share the same antennas (e.g., of an RU **170**) of an IAB node **104** used for access via the DU **165** of the IAB node **104** (e.g., referred to as virtual IAB-MT (vIAB-MT)). In some examples, the IAB nodes **104** may include DUs **165** that support communication links with additional entities (e.g., IAB nodes **104**, UEs **115**) within the relay chain or configuration of the access network (e.g., downstream). In such cases, one or more components of the disaggregated RAN architecture (e.g., one or more IAB nodes **104** or components of IAB nodes **104**) may be configured to operate according to the techniques described herein.

[0064] For instance, an access network (AN) or RAN may include communications between access nodes (e.g., an IAB donor), IAB nodes **104**, and one or more UEs **115**. The IAB donor may facilitate connection between the core network **130** and the AN (e.g., via a wired or wireless connection to the core network **130**). That is, an IAB donor may refer to a RAN node with a wired or wireless connection to core network **130**. The IAB donor may include a CU **160** and at least one DU **165** (e.g., and RU **170**), in which case the CU **160** may communicate with the core network **130** via an interface (e.g., a backhaul link). IAB donor and IAB nodes **104** may communicate via an F1 interface according to a protocol that defines signaling messages (e.g., an F1 AP protocol). Additionally, or alternatively, the CU **160** may communicate with the core network via an interface, which may be an example of a portion of backhaul link, and may communicate with other CUs **160** (e.g., a CU **160** associated with an alternative IAB donor) via an Xn-C interface, which may be an example of a portion of a backhaul link.

[0065] An IAB node **104** may refer to a RAN node that provides IAB functionality (e.g., access for UEs **115**, wireless self-backhauling capabilities). A DU **165** may act as a distributed scheduling node towards child nodes associated with the IAB node **104**, and the IAB-MT may act as a scheduled node towards parent nodes associated with the IAB node **104**. That is, an IAB donor may be referred to as a parent node in communication with one or more child nodes (e.g., an IAB donor may relay transmissions for UEs through one or more other IAB nodes **104**). Additionally, or alternatively, an IAB node **104** may also be referred to as a parent node or a child node to other IAB nodes **104**, depending on the relay chain or configuration of the AN. Therefore, the IAB-MT entity of IAB nodes **104** may provide a Uu interface for a child IAB node **104** to receive signaling from a parent IAB node **104**, and the DU interface (e.g., DUs **165**) may provide a Uu interface for a parent IAB node **104** to signal to a child IAB node **104** or UE **115**.

[0066] For example, IAB node **104** may be referred to as a parent node that supports communications for a child IAB node, or IAB node **104** may be referred to as a child IAB node associated with an IAB donor, or both. The IAB donor may include a CU **160** with a wired or wireless connection (e.g., a backhaul communication link **120**) to the core network **130** and may act

as parent node to IAB nodes **104**. For example, the DU **165** of IAB donor may relay transmissions to UEs **115** through IAB nodes **104**, or may directly signal transmissions to a UE **115**, or both. The CU **160** of IAB donor may signal communication link establishment via an F1 interface to IAB nodes **104**, and the IAB nodes **104** may schedule transmissions (e.g., transmissions to the UEs **115** relayed from the IAB donor) through the DUs **165**. That is, data may be relayed to and from IAB nodes **104** via signaling via an NR Uu interface to MT of the IAB node **104**. Communications with IAB node **104** may be scheduled by a DU **165** of IAB donor and communications with IAB node **104** may be scheduled by DU **165** of IAB node **104**.

[0067] In the case of the techniques described herein applied in the context of a disaggregated RAN architecture, one or more components of the disaggregated RAN architecture may be configured to support frequency resource selection for multiple channels as described herein. For example, some operations described as being performed by a UE **115** or a network entity **105** (e.g., a base station **140**) may additionally, or alternatively, be performed by one or more components of the disaggregated RAN architecture (e.g., IAB nodes **104**, DUs **165**, CUs **160**, RUs **170**, RIC **175**, SMO **180**).

[0068] A UE **115** may include or may be referred to as a mobile device, a wireless device, a remote device, a handheld device, or a subscriber device, or some other suitable terminology, where the “device” may also be referred to as a unit, a station, a terminal, or a client, among other examples. A UE **115** may also include or may be referred to as a personal electronic device such as a cellular phone, a personal digital assistant (PDA), a tablet computer, a laptop computer, or a personal computer. In some examples, a UE **115** may include or be referred to as a wireless local loop (WLL) station, an Internet of Things (IoT) device, an Internet of Everything (IoE) device, or a machine type communications (MTC) device, among other examples, which may be implemented in various objects such as appliances, or vehicles, meters, among other examples.

[0069] The UEs **115** described herein may be able to communicate with various types of devices, such as other UEs **115** that may sometimes act as relays as well as the network entities **105** and the network equipment including macro eNBs or gNBs, small cell eNBs or gNBs, or relay base stations, among other examples, as shown in FIG. **1**.

[0070] The UEs **115** and the network entities **105** may wirelessly communicate with one another via one or more communication links **125** (e.g., an access link) using resources associated with one or more carriers. The term “carrier” may refer to a set of RF spectrum resources having a defined physical layer structure for supporting the communication links **125**. For example, a carrier used for a communication link **125** may include a portion of a RF spectrum band (e.g., a bandwidth part (BWP)) that is operated according to one or more physical layer channels for a given radio access technology (e.g., LTE, LTE-A, LTE-A Pro, NR). Each physical layer channel may carry acquisition signaling (e.g., synchronization signals, system information), control signaling that coordinates operation for the carrier, user data, or other signaling. The wireless communications system **100** may support communication with a UE **115** using carrier aggregation or multi-carrier operation. A UE **115** may be configured with multiple downlink component carriers and one or more uplink component carriers according to a carrier aggregation configuration. Carrier aggregation may be used with both frequency division duplexing (FDD) and time division duplexing (TDD) component carriers. Communication between a network entity **105** and other devices may refer to communication between the devices and any portion (e.g., entity, sub-entity) of a network entity **105**. For example, the terms “transmitting,” “receiving,” or “communicating,” when referring to a network entity **105**, may refer to any portion of a network entity **105** (e.g., a base station **140**, a CU **160**, a DU **165**, a RU **170**) of a RAN communicating with another device (e.g., directly or via one or more other network entities **105**).

[0071] In some examples, such as in a carrier aggregation configuration, a carrier may also have acquisition signaling or control signaling that coordinates operations for other carriers. A carrier may be associated with a frequency channel (e.g., an evolved universal mobile telecommunication

system terrestrial radio access (E-UTRA) absolute RF channel number (EARFCN)) and may be identified according to a channel raster for discovery by the UEs **115**. A carrier may be operated in a standalone mode, in which case initial acquisition and connection may be conducted by the UEs **115** via the carrier, or the carrier may be operated in a non-standalone mode, in which case a connection is anchored using a different carrier (e.g., of the same or a different radio access technology).

[0072] The communication links **125** shown in the wireless communications system **100** may include downlink transmissions (e.g., forward link transmissions) from a network entity **105** to a UE **115**, uplink transmissions (e.g., return link transmissions) from a UE **115** to a network entity **105**, or both, among other configurations of transmissions. Carriers may carry downlink or uplink communications (e.g., in an FDD mode) or may be configured to carry downlink and uplink communications (e.g., in a TDD mode).

[0073] A carrier may be associated with a particular bandwidth of the RF spectrum and, in some examples, the carrier bandwidth may be referred to as a “system bandwidth” of the carrier or the wireless communications system **100**. For example, the carrier bandwidth may be one of a set of bandwidths for carriers of a particular radio access technology (e.g., 1.4, 3, 5, 10, 15, 20, 40, or 80 megahertz (MHz)). Devices of the wireless communications system **100** (e.g., the network entities **105**, the UEs **115**, or both) may have hardware configurations that support communications using a particular carrier bandwidth or may be configurable to support communications using one of a set of carrier bandwidths. In some examples, the wireless communications system **100** may include network entities **105** or UEs **115** that support concurrent communications using carriers associated with multiple carrier bandwidths. In some examples, each served UE **115** may be configured for operating using portions (e.g., a sub-band, a BWP) or all of a carrier bandwidth.

[0074] Signal waveforms transmitted via a carrier may be made up of multiple subcarriers (e.g., using multi-carrier modulation (MCM) techniques such as orthogonal frequency division multiplexing (OFDM) or discrete Fourier transform spread OFDM (DFT-S-OFDM)). In a system employing MCM techniques, a resource element may refer to resources of one symbol period (e.g., a duration of one modulation symbol) and one subcarrier, in which case the symbol period and subcarrier spacing may be inversely related. The quantity of bits carried by each resource element may depend on the modulation scheme (e.g., the order of the modulation scheme, the coding rate of the modulation scheme, or both), such that a relatively higher quantity of resource elements (e.g., in a transmission duration) and a relatively higher order of a modulation scheme may correspond to a relatively higher rate of communication. A wireless communications resource may refer to a combination of an RF spectrum resource, a time resource, and a spatial resource (e.g., a spatial layer, a beam), and the use of multiple spatial resources may increase the data rate or data integrity for communications with a UE **115**.

[0075] One or more numerologies for a carrier may be supported, and a numerology may include a subcarrier spacing (Δf) and a cyclic prefix. A carrier may be divided into one or more BWPs having the same or different numerologies. In some examples, a UE **115** may be configured with multiple BWPs. In some examples, a single BWP for a carrier may be active at a given time and communications for the UE **115** may be restricted to one or more active BWPs.

[0076] The time intervals for the network entities **105** or the UEs **115** may be expressed in multiples of a basic time unit which may, for example, refer to a sampling period of $T_{\text{sub.s}} = 1/(\Delta f_{\text{sub.max}} \cdot N_{\text{sub.f}})$ seconds, for which $\Delta f_{\text{sub.max}}$ may represent a supported subcarrier spacing, and $N_{\text{sub.f}}$ may represent a supported discrete Fourier transform (DFT) size. Time intervals of a communications resource may be organized according to radio frames each having a specified duration (e.g., 10 milliseconds (ms)). Each radio frame may be identified by a system frame number (SFN) (e.g., ranging from 0 to 1023).

[0077] Each frame may include multiple consecutively numbered subframes or slots, and each subframe or slot may have the same duration. In some examples, a frame may be divided (e.g., in

the time domain) into subframes, and each subframe may be further divided into a quantity of slots. Alternatively, each frame may include a variable quantity of slots, and the quantity of slots may depend on subcarrier spacing. Each slot may include a quantity of symbol periods (e.g., depending on the length of the cyclic prefix prepended to each symbol period). In some wireless communications systems **100**, a slot may further be divided into multiple mini-slots associated with one or more symbols. Excluding the cyclic prefix, each symbol period may be associated with one or more (e.g., $N_{\text{sub.f}}$) sampling periods. The duration of a symbol period may depend on the subcarrier spacing or frequency band of operation.

[0078] A subframe, a slot, a mini-slot, or a symbol may be the smallest scheduling unit (e.g., in the time domain) of the wireless communications system **100** and may be referred to as a transmission time interval (TTI). In some examples, the TTI duration (e.g., a quantity of symbol periods in a TTI) may be variable. Additionally, or alternatively, the smallest scheduling unit of the wireless communications system **100** may be dynamically selected (e.g., in bursts of shortened TTIs (sTTIs)).

[0079] Physical channels may be multiplexed for communication using a carrier according to various techniques. A physical control channel and a physical data channel may be multiplexed for signaling via a downlink carrier, for example, using one or more of time division multiplexing (TDM) techniques, frequency division multiplexing (FDM) techniques, or hybrid TDM-FDM techniques. A control region (e.g., a control resource set (CORESET)) for a physical control channel may be defined by a set of symbol periods and may extend across the system bandwidth or a subset of the system bandwidth of the carrier. One or more control regions (e.g., CORESETs) may be configured for a set of the UEs **115**. For example, one or more of the UEs **115** may monitor or search control regions for control information according to one or more search space sets, and each search space set may include one or multiple control channel candidates in one or more aggregation levels arranged in a cascaded manner. An aggregation level for a control channel candidate may refer to an amount of control channel resources (e.g., control channel elements (CCEs)) associated with encoded information for a control information format having a given payload size. Search space sets may include common search space sets configured for sending control information to multiple UEs **115** and UE-specific search space sets for sending control information to a specific UE **115**.

[0080] A network entity **105** may provide communication coverage via one or more cells, for example a macro cell, a small cell, a hot spot, or other types of cells, or any combination thereof. The term “cell” may refer to a logical communication entity used for communication with a network entity **105** (e.g., using a carrier) and may be associated with an identifier for distinguishing neighboring cells (e.g., a physical cell identifier (PCID), a virtual cell identifier (VCID), or others). In some examples, a cell also may refer to a coverage area **110** or a portion of a coverage area **110** (e.g., a sector) over which the logical communication entity operates. Such cells may range from smaller areas (e.g., a structure, a subset of structure) to larger areas depending on various factors such as the capabilities of the network entity **105**. For example, a cell may be or include a building, a subset of a building, or exterior spaces between or overlapping with coverage areas **110**, among other examples.

[0081] A macro cell generally covers a relatively large geographic area (e.g., several kilometers in radius) and may allow unrestricted access by the UEs **115** with service subscriptions with the network provider supporting the macro cell. A small cell may be associated with a lower-powered network entity **105** (e.g., a lower-powered base station **140**), as compared with a macro cell, and a small cell may operate using the same or different (e.g., licensed, unlicensed) frequency bands as macro cells. Small cells may provide unrestricted access to the UEs **115** with service subscriptions with the network provider or may provide restricted access to the UEs **115** having an association with the small cell (e.g., the UEs **115** in a closed subscriber group (CSG), the UEs **115** associated with users in a home or office). A network entity **105** may support one or multiple cells and may

also support communications via the one or more cells using one or multiple component carriers.

[0082] In some examples, a carrier may support multiple cells, and different cells may be configured according to different protocol types (e.g., MTC, narrowband IoT (NB-IoT), enhanced mobile broadband (eMBB)) that may provide access for different types of devices.

[0083] In some examples, a network entity **105** (e.g., a base station **140**, an RU **170**) may be movable and therefore provide communication coverage for a moving coverage area **110**. In some examples, different coverage areas **110** associated with different technologies may overlap, but the different coverage areas **110** may be supported by the same network entity **105**. In some other examples, the overlapping coverage areas **110** associated with different technologies may be supported by different network entities **105**. The wireless communications system **100** may include, for example, a heterogeneous network in which different types of the network entities **105** provide coverage for various coverage areas **110** using the same or different radio access technologies.

[0084] The wireless communications system **100** may support synchronous or asynchronous operation. For synchronous operation, network entities **105** (e.g., base stations **140**) may have similar frame timings, and transmissions from different network entities **105** may be approximately aligned in time. For asynchronous operation, network entities **105** may have different frame timings, and transmissions from different network entities **105** may, in some examples, not be aligned in time. The techniques described herein may be used for either synchronous or asynchronous operations.

[0085] Some UEs **115**, such as MTC or IoT devices, may be low cost or low complexity devices and may provide for automated communication between machines (e.g., via Machine-to-Machine (M2M) communication). M2M communication or MTC may refer to data communication technologies that allow devices to communicate with one another or a network entity **105** (e.g., a base station **140**) without human intervention. In some examples, M2M communication or MTC may include communications from devices that integrate sensors or meters to measure or capture information and relay such information to a central server or application program that uses the information or presents the information to humans interacting with the application program. Some UEs **115** may be designed to collect information or enable automated behavior of machines or other devices. Examples of applications for MTC devices include smart metering, inventory monitoring, water level monitoring, equipment monitoring, healthcare monitoring, wildlife monitoring, weather and geological event monitoring, fleet management and tracking, remote security sensing, physical access control, and transaction-based business charging.

[0086] Some UEs **115** may be configured to employ operating modes that reduce power consumption, such as half-duplex communications (e.g., a mode that supports one-way communication via transmission or reception, but not transmission and reception concurrently). In some examples, half-duplex communications may be performed at a reduced peak rate. Other power conservation techniques for the UEs **115** include entering a power saving deep sleep mode when not engaging in active communications, operating using a limited bandwidth (e.g., according to narrowband communications), or a combination of these techniques. For example, some UEs **115** may be configured for operation using a narrowband protocol type that is associated with a defined portion or range (e.g., set of subcarriers or resource blocks (RBs)) within a carrier, within a guard-band of a carrier, or outside of a carrier.

[0087] The wireless communications system **100** may be configured to support ultra-reliable communications or low-latency communications, or various combinations thereof. For example, the wireless communications system **100** may be configured to support ultra-reliable low-latency communications (URLLC). The UEs **115** may be designed to support ultra-reliable, low-latency, or critical functions. Ultra-reliable communications may include private communication or group communication and may be supported by one or more services such as push-to-talk, video, or data. Support for ultra-reliable, low-latency functions may include prioritization of services, and such services may be used for public safety or general commercial applications. The terms ultra-reliable,

low-latency, and ultra-reliable low-latency may be used interchangeably herein.

[0088] In some examples, a UE **115** may be configured to support communicating directly with other UEs **115** via a device-to-device (D2D) communication link **135** (e.g., in accordance with a peer-to-peer (P2P), D2D, or sidelink protocol). In some examples, one or more UEs **115** of a group that are performing D2D communications may be within the coverage area **110** of a network entity **105** (e.g., a base station **140**, an RU **170**), which may support aspects of such D2D communications being configured by (e.g., scheduled by) the network entity **105**. In some examples, one or more UEs **115** of such a group may be outside the coverage area **110** of a network entity **105** or may be otherwise unable to or not configured to receive transmissions from a network entity **105**. In some examples, groups of the UEs **115** communicating via D2D communications may support a one-to-many (1:M) system in which each UE **115** transmits to each of the other UEs **115** in the group. In some examples, a network entity **105** may facilitate the scheduling of resources for D2D communications. In some other examples, D2D communications may be carried out between the UEs **115** without an involvement of a network entity **105**.

[0089] In some systems, a D2D communication link **135** may be an example of a communication channel, such as a sidelink communication channel, between vehicles (e.g., UEs **115**). In some examples, vehicles may communicate using vehicle-to-everything (V2X) communications, vehicle-to-vehicle (V2V) communications, or some combination of these. A vehicle may signal information related to traffic conditions, signal scheduling, weather, safety, emergencies, or any other information relevant to a V2X system. In some examples, vehicles in a V2X system may communicate with roadside infrastructure, such as roadside units, or with the network via one or more network nodes (e.g., network entities **105**, base stations **140**, RUs **170**) using vehicle-to-network (V2N) communications, or with both.

[0090] The core network **130** may provide user authentication, access authorization, tracking, Internet Protocol (IP) connectivity, and other access, routing, or mobility functions. The core network **130** may be an evolved packet core (EPC) or 5G core (5GC), which may include at least one control plane entity that manages access and mobility (e.g., a mobility management entity (MME), an access and mobility management function (AMF)) and at least one user plane entity that routes packets or interconnects to external networks (e.g., a serving gateway (S-GW), a Packet Data Network (PDN) gateway (P-GW), or a user plane function (UPF)). The control plane entity may manage non-access stratum (NAS) functions such as mobility, authentication, and bearer management for the UEs **115** served by the network entities **105** (e.g., base stations **140**) associated with the core network **130**. User IP packets may be transferred through the user plane entity, which may provide IP address allocation as well as other functions. The user plane entity may be connected to IP services **150** for one or more network operators. The IP services **150** may include access to the Internet, Intranet(s), an IP Multimedia Subsystem (IMS), or a Packet-Switched Streaming Service.

[0091] The wireless communications system **100** may operate using one or more frequency bands, which may be in the range of 300 megahertz (MHz) to 300 gigahertz (GHz). Generally, the region from 300 MHz to 3 GHz is known as the ultra-high frequency (UHF) region or decimeter band because the wavelengths range from approximately one decimeter to one meter in length. UHF waves may be blocked or redirected by buildings and environmental features, which may be referred to as clusters, but the waves may penetrate structures sufficiently for a macro cell to provide service to the UEs **115** located indoors. Communications using UHF waves may be associated with smaller antennas and shorter ranges (e.g., less than 100 kilometers) compared to communications using the smaller frequencies and longer waves of the high frequency (HF) or very high frequency (VHF) portion of the spectrum below 300 MHz.

[0092] The wireless communications system **100** may also operate using a super high frequency (SHF) region, which may be in the range of 3 GHz to 30 GHz, also known as the centimeter band, or using an extremely high frequency (EHF) region of the spectrum (e.g., from 30 GHz to 300

GHz), also known as the millimeter band. In some examples, the wireless communications system **100** may support millimeter wave (mmW) communications between the UEs **115** and the network entities **105** (e.g., base stations **140**, RUs **170**), and EHF antennas of the respective devices may be smaller and more closely spaced than UHF antennas. In some examples, such techniques may facilitate using antenna arrays within a device. The propagation of EHF transmissions, however, may be subject to even greater attenuation and shorter range than SHF or UHF transmissions. The techniques disclosed herein may be employed across transmissions that use one or more different frequency regions, and designated use of bands across these frequency regions may differ by country or regulating body.

[0093] The wireless communications system **100** may utilize both licensed and unlicensed RF spectrum bands. For example, the wireless communications system **100** may employ License Assisted Access (LAA), LTE-Unlicensed (LTE-U) radio access technology, or NR technology using an unlicensed band such as the 5 GHz industrial, scientific, and medical (ISM) band. While operating using unlicensed RF spectrum bands, devices such as the network entities **105** and the UEs **115** may employ carrier sensing for collision detection and avoidance. In some examples, operations using unlicensed bands may be based on a carrier aggregation configuration in conjunction with component carriers operating using a licensed band (e.g., LAA). Operations using unlicensed spectrum may include downlink transmissions, uplink transmissions, P2P transmissions, or D2D transmissions, among other examples.

[0094] A network entity **105** (e.g., a base station **140**, an RU **170**) or a UE **115** may be equipped with multiple antennas, which may be used to employ techniques such as transmit diversity, receive diversity, multiple-input multiple-output (MIMO) communications, or beamforming. The antennas of a network entity **105** or a UE **115** may be located within one or more antenna arrays or antenna panels, which may support MIMO operations or transmit or receive beamforming. For example, one or more base station antennas or antenna arrays may be co-located at an antenna assembly, such as an antenna tower. In some examples, antennas or antenna arrays associated with a network entity **105** may be located at diverse geographic locations. A network entity **105** may include an antenna array with a set of rows and columns of antenna ports that the network entity **105** may use to support beamforming of communications with a UE **115**. Likewise, a UE **115** may include one or more antenna arrays that may support various MIMO or beamforming operations. Additionally, or alternatively, an antenna panel may support RF beamforming for a signal transmitted via an antenna port.

[0095] The network entities **105** or the UEs **115** may use MIMO communications to exploit multipath signal propagation and increase spectral efficiency by transmitting or receiving multiple signals via different spatial layers. Such techniques may be referred to as spatial multiplexing. The multiple signals may, for example, be transmitted by the transmitting device via different antennas or different combinations of antennas. Likewise, the multiple signals may be received by the receiving device via different antennas or different combinations of antennas. Each of the multiple signals may be referred to as a separate spatial stream and may carry information associated with the same data stream (e.g., the same codeword) or different data streams (e.g., different codewords). Different spatial layers may be associated with different antenna ports used for channel measurement and reporting. MIMO techniques include single-user MIMO (SU-MIMO), for which multiple spatial layers are transmitted to the same receiving device, and multiple-user MIMO (MU-MIMO), for which multiple spatial layers are transmitted to multiple devices.

[0096] Beamforming, which may also be referred to as spatial filtering, directional transmission, or directional reception, is a signal processing technique that may be used at a transmitting device or a receiving device (e.g., a network entity **105**, a UE **115**) to shape or steer an antenna beam (e.g., a transmit beam, a receive beam) along a spatial path between the transmitting device and the receiving device. Beamforming may be achieved by combining the signals communicated via antenna elements of an antenna array such that some signals propagating along particular

orientations with respect to an antenna array experience constructive interference while others experience destructive interference. The adjustment of signals communicated via the antenna elements may include a transmitting device or a receiving device applying amplitude offsets, phase offsets, or both to signals carried via the antenna elements associated with the device. The adjustments associated with each of the antenna elements may be defined by a beamforming weight set associated with a particular orientation (e.g., with respect to the antenna array of the transmitting device or receiving device, or with respect to some other orientation).

[0097] A network entity **105** or a UE **115** may use beam sweeping techniques as part of beamforming operations. For example, a network entity **105** (e.g., a base station **140**, an RU **170**) may use multiple antennas or antenna arrays (e.g., antenna panels) to conduct beamforming operations for directional communications with a UE **115**. Some signals (e.g., synchronization signals, reference signals, beam selection signals, or other control signals) may be transmitted by a network entity **105** multiple times along different directions. For example, the network entity **105** may transmit a signal according to different beamforming weight sets associated with different directions of transmission. Transmissions along different beam directions may be used to identify (e.g., by a transmitting device, such as a network entity **105**, or by a receiving device, such as a UE **115**) a beam direction for later transmission or reception by the network entity **105**.

[0098] Some signals, such as data signals associated with a particular receiving device, may be transmitted by transmitting device (e.g., a transmitting network entity **105**, a transmitting UE **115**) along a single beam direction (e.g., a direction associated with the receiving device, such as a receiving network entity **105** or a receiving UE **115**). In some examples, the beam direction associated with transmissions along a single beam direction may be determined based on a signal that was transmitted along one or more beam directions. For example, a UE **115** may receive one or more of the signals transmitted by the network entity **105** along different directions and may report to the network entity **105** an indication of the signal that the UE **115** received with a highest signal quality or an otherwise acceptable signal quality.

[0099] In some examples, transmissions by a device (e.g., by a network entity **105** or a UE **115**) may be performed using multiple beam directions, and the device may use a combination of digital precoding or beamforming to generate a combined beam for transmission (e.g., from a network entity **105** to a UE **115**). The UE **115** may report feedback that indicates precoding weights for one or more beam directions, and the feedback may correspond to a configured set of beams across a system bandwidth or one or more sub-bands. The network entity **105** may transmit a reference signal (e.g., a cell-specific reference signal (CRS), a channel state information reference signal (CSI-RS)), which may be precoded or unprecoded. The UE **115** may provide feedback for beam selection, which may be a precoding matrix indicator (PMI) or codebook-based feedback (e.g., a multi-panel type codebook, a linear combination type codebook, a port selection type codebook). Although these techniques are described with reference to signals transmitted along one or more directions by a network entity **105** (e.g., a base station **140**, an RU **170**), a UE **115** may employ similar techniques for transmitting signals multiple times along different directions (e.g., for identifying a beam direction for subsequent transmission or reception by the UE **115**) or for transmitting a signal along a single direction (e.g., for transmitting data to a receiving device).

[0100] A receiving device (e.g., a UE **115**) may perform reception operations in accordance with multiple receive configurations (e.g., directional listening) when receiving various signals from a receiving device (e.g., a network entity **105**), such as synchronization signals, reference signals, beam selection signals, or other control signals. For example, a receiving device may perform reception in accordance with multiple receive directions by receiving via different antenna subarrays, by processing received signals according to different antenna subarrays, by receiving according to different receive beamforming weight sets (e.g., different directional listening weight sets) applied to signals received at multiple antenna elements of an antenna array, or by processing received signals according to different receive beamforming weight sets applied to signals received

at multiple antenna elements of an antenna array, any of which may be referred to as “listening” according to different receive configurations or receive directions. In some examples, a receiving device may use a single receive configuration to receive along a single beam direction (e.g., when receiving a data signal). The single receive configuration may be aligned along a beam direction determined based on listening according to different receive configuration directions (e.g., a beam direction determined to have a highest signal strength, highest signal-to-noise ratio (SNR), or otherwise acceptable signal quality based on listening according to multiple beam directions).

[0101] The wireless communications system **100** may be a packet-based network that operates according to a layered protocol stack. In the user plane, communications at the bearer or PDCP layer may be IP-based. An RLC layer may perform packet segmentation and reassembly to communicate via logical channels. A MAC layer may perform priority handling and multiplexing of logical channels into transport channels. The MAC layer also may implement error detection techniques, error correction techniques, or both to support retransmissions to improve link efficiency. In the control plane, an RRC layer may provide establishment, configuration, and maintenance of an RRC connection between a UE **115** and a network entity **105** or a core network **130** supporting radio bearers for user plane data. A PHY layer may map transport channels to physical channels.

[0102] The UEs **115** and the network entities **105** may support retransmissions of data to increase the likelihood that data is received successfully. Hybrid automatic repeat request (HARQ) feedback is one technique for increasing the likelihood that data is received correctly via a communication link (e.g., a communication link **125**, a D2D communication link **135**). HARQ may include a combination of error detection (e.g., using a cyclic redundancy check (CRC)), forward error correction (FEC), and retransmission (e.g., automatic repeat request (ARQ)). HARQ may improve throughput at the MAC layer in poor radio conditions (e.g., low signal-to-noise conditions). In some examples, a device may support same-slot HARQ feedback, in which case the device may provide HARQ feedback in a specific slot for data received via a previous symbol in the slot. In some other examples, the device may provide HARQ feedback in a subsequent slot, or according to some other time interval.

[0103] The wireless communications system **100** may support frequency resource selection for multiple channels. For example, a network entity **105** may schedule multiple channels having different frequency resource allocations and a UE may select at least one channel from among the multiple allocated channels. The UE **115** may receive scheduling information that allocates the multiple channels having a same channel type. The channel type may be uplink, downlink, shared channel, control channel, or any combination thereof. Allocation of a channel may include allocation of a set of channel resources. In some aspects, the scheduling information may allocate a respective set of frequency sources for each of the multiple channels. Allocation of multiple sets of overlapping or non-overlapping frequency resources may improve communication reliability due to frequency diversity among the allocated resources, for example.

[0104] If the scheduling information allocates multiple uplink channels, the network entity **105** may transmit an indication that uplink channel selection by the UE **115** is enabled for the multiple uplink channels. In such cases, the UE **115** may select at least a first uplink channel from among the multiple uplink channels allocated via the scheduling information. The first uplink channel may be associated with or may include a first set of frequency resources. The UE **115** may transmit an uplink message and an indication of the selection via the first uplink channel based on the selection. The UE **115** may refrain from transmitting via at least a portion of one or more other uplink channels of the set of multiple uplink channels allocated via the scheduling information based on the selection. The UE **115** may thereby refrain from transmitting excessive information if uplink channel resources are overallocated, which may reduce processing, power consumption, and overhead.

[0105] FIG. 2 illustrates an example of a wireless communications system **200** that supports

frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The wireless communications system **200** may implement or be implemented by aspects of the wireless communications system **100**. For example, the wireless communications system **200** illustrates communications between a UE **115-a** and a network entity **105-a**, which may represent examples of corresponding devices as described with reference to FIG. 1.

[0106] The network entity **105-a** may communicate with the UE **115-a** within a geographic coverage area **110-a** and via one or more downlink communication links **205** and one or more uplink communication links **210**. The network entity **105-a** may transmit scheduling information **215** to schedule resources for uplink transmissions by the UE **115-a** via an uplink communication link **210**, downlink transmissions to the UE **115-a** via a downlink communication link **205**, or both. The scheduling information **215** may be transmitted via a dynamic grant (e.g., a DCI), one or more configured grants, or both.

[0107] In some aspects, communications between the UE **115-a** and the network entity **105-a** may follow a somewhat regular or periodic pattern, and may occur relatively frequently (e.g., extended reality (XR) communications). For example, the UE **115-a**, the network entity **105-a**, or both may support one or more applications (e.g., cloud gaming applications, XR applications, virtual reality (VR) split rendering applications, augmented reality (AR) split computation applications, some other applications, or any combination thereof) that may be associated with relatively frequent (e.g., low latency) uplink or downlink traffic that has a regular or periodic pattern. In some aspects, the traffic, such as uplink video traffic, may include bursts of data packets. A burst may correspond to a relatively large quantity of data packets being transmitted within a relatively short period of time (e.g., a set of packets generated by one or more applications at roughly the same time).

[0108] The network entity **105-a** may support such bursts of uplink or downlink data by allocating, via the scheduling information **215** (e.g., a single DCI), multiple uplink or downlink channels of a same channel type (e.g., multi-PUSCH transmissions or multi-PDSCH transmissions). The channel type may correspond to a PUSCH, a PDSCH, a physical uplink control channel (PUCCH), a physical downlink control channel (PDCCH), some other type of uplink or downlink channel, or any combination thereof. In some aspects, allocation of an uplink channel or a downlink channel may correspond to allocation of a set of channel resources in time and frequency domains. For example, allocation of two PUSCHs may correspond to an allocation of a first set of PUSCH resources and a second set of PUSCH resources. The first and second sets of PUSCH resources may be overlapping or non-overlapping in the time domain and the frequency domain. The multiple channels may be allocated within a same downlink communication link **205** or uplink communication link **210**, or within different communication links (e.g., as illustrated by the dashed arrows in FIG. 2).

[0109] The network entity **105-a** may schedule the multiple uplink or downlink channels across multiple slots, multiple cells, or both. For example, the network entity **105-a** may transmit scheduling information **215** via one or more grants to allocate resources for transmitting multiple transport blocks (TBs) in different slots in uplink and/or downlink directions. The multiple uplink or downlink channels may be configured with a same modulation and coding scheme (MCS) or bandwidth for all the scheduled TBs. The grant may include a TDRA field that supports allocation of multiple sets of time resources that are non-overlapping or partially overlapping in the time domain. Each allocated uplink or downlink channel may thereby be configured with a different starting position or slot. In some cases, however, if the scheduling information **215** is transmitted via a single grant (e.g., for dynamic grants), a frequency allocation for each of the scheduled channels may be the same. For example, an FDRA field in the grant may not support allocation of different frequency resources, which may reduce reliability of the scheduled transmissions due to lack of frequency diversity among the allocated channel resources, for example.

[0110] Techniques, systems, and devices described herein provide for the network entity **105-a** to schedule multiple channels having different frequency resource allocations using one or more

configured grants, a dynamic grant, or both. For example, an FDRA field in the dynamic grant may be added or updated to support multiple frequency resource allocations. Techniques for allocating multiple different sets of frequency resources via a single grant are described in further detail elsewhere herein, including with reference to FIG. 3.

[0111] In some cases, the UE **115-a** may transmit a scheduling request, a buffer status report (BSR), or both to the network entity **105-a** to request resources for an uplink transmission. The network entity **105-a** may transmit the scheduling information **215** that allocates uplink channel resources for the UE **115-a** based on the scheduling request, the BSR, or both. In some cases, however, transmission of the scheduling information and BSR may increase a round-trip-time for communications, which may increase latency. As such, the network entity **105-a** may, in some aspects, preschedule uplink channels for the UE **115-a** (e.g., in anticipation of new uplink data and without receiving a request from the UE **115-a**).

[0112] If the network entity **105-a** preschedules uplink channels, the network entity **105-a** may over-allocate uplink resources for the UE **115-a** (e.g., as the network entity **105-a** may allocate the resources without knowledge of how much uplink information is in a buffer at the UE **115-a**). Additionally, or alternatively, the network entity **105-a** may over-allocate uplink resources due to quantization errors or relatively low resolution associated with a BSR from the UE **115-a** (e.g., the uplink grants may not match the data at the UE **115-a**). In such cases, the network entity **105-a** may allocate multiple sets of uplink resources for a single transmission, and the UE **115-a** may be able to transmit all the information in the buffer of the UE **115-a** in fewer than all of the allocated resources. In some cases, the UE **115-a** may be configured to transmit in all of the allocated resources, regardless of a capacity of the buffer at the UE **115-a**. For example, the UE **115-a** may transmit zeroes or other filler information to fill all of the allocated resources, which may increase overhead and power consumption by the UE **115-a**.

[0113] Techniques described herein provide for the UE **115-a** to select a subset of the uplink channel resources allocated via the scheduling information **215** and to indicate the selection to the network entity **105-a**. The UE **115-a** may refrain from transmitting via remaining uplink channel resources that were allocated via the scheduling information **215** but not selected by the UE **115-a**, which may reduce power compensation and overhead. In some aspects, the UE **115-a** may receive an indication that uplink channel selection is enabled. The indication may be transmitted via the scheduling information **215** (e.g., DCI) or a control message that is different than the scheduling information **215** (e.g., an RRC message, a medium access control-control element (MAC-CE), DCI, or some other control message). The indication may be a bit that, when set to a certain value, signals that the UE **115-a** may choose one or a subset of the multiple uplink channels allocated via the scheduling information **215**. Additionally, or alternatively, the scheduling information **215** may be transmitted via DCI and a format of the DCI may indicate that the uplink channel selection by the UE **115-a** is enabled.

[0114] If uplink channel selection by the UE **115-a** is enabled or configured, the UE **115-a** may select one or more uplink channels, or a subset of resources within one or more uplink channels, from the scheduled uplink channels to use for transmitting an uplink message **220**. The UE **115-a** may select the uplink channels or the portions of uplink channels based on a quantity of data in a buffer at the UE **115-a** (e.g., a size of the uplink message **220**). To reduce blind detection by the network entity **105-a**, the UE **115-a** may transmit, via the selected uplink resources, a channel selection indication **225** to indicate the selected set of resources to the network entity **105-a**. The channel selection indication **225** may be transmitted via UCI, a DMRS sequence, some other uplink message or reference signal, or any combination thereof. Techniques for indicating the uplink resource selection are described in further detail elsewhere herein, including with reference to FIGS. 4-6.

[0115] The UE **115-a** may transmit the uplink message **220** via the selected set of uplink resources. The UE **115-a** may refrain from transmitting the uplink message **220** or any other uplink message

or signaling via the other uplink resources that were allocated via the scheduling information **215** but were not selected by the UE **115-a**. Thus, the UE **115-a** may refrain from transmitting extra information (e.g., null information) via overallocated resources, which may reduce power consumption and overhead. The UE **115-a** and the network entity **105-a** may thereby support communications via multiple uplink or downlink channels allocated by the same scheduling information **215** and having the same or different frequency resource allocations. By selecting one or more of the allocated channels, the UE **115-a** may reduce power consumption and overhead.

[0116] FIG. 3 illustrates an example of a channel configuration scheme **300** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The channel configuration scheme **300** may implement or be implemented by aspects of the wireless communications systems **100** and **200** described with reference to FIGS. 1 and 2. For example, the channel configuration scheme **300** illustrates a configuration of multiple channels **320** for uplink or downlink communications between a UE **115** and a network entity **105**, which may represent examples of corresponding devices as described with reference to FIGS. 1 and 2.

[0117] The network entity **105** may schedule or allocate multiple channels **320** each including a respective set of channel resources **305** for communications with the UE **115**. The network entity **105** may indicate the scheduled channels **320** via scheduling information **315** in a dynamic grant (e.g., DCI) or one or more configured grants. The channels **320** may be uplink channels (e.g., a PUSCH), downlink channels (e.g., a PDSCH), or both. Allocation of a channel **320** as described herein may include allocation of a set of channel resources **305** in a time domain and a frequency domain, as illustrated in FIG. 2. For example, the channel **320-a** may include a first set of channel resources **305** that is different than (e.g., partially but not fully overlapping with) a second set of channel resources **305** allocated for the channel **320-b** and a third set of channel resources **305** allocated for the channel **320-c**. In some aspects, the scheduling information **315** may schedule channels **320** of a same channel type. For example, the channels **320** may each be uplink shared channels or downlink shared channels.

[0118] The channels **320** scheduled by the scheduling information **315** may be overlapping, non-overlapping, or partially overlapping in a time domain. In some aspects, if the scheduling information **315** is transmitted via a single grant **310** (e.g., DCI), the grant **310** may schedule multiple starting positions for uplink or downlink transmissions in one or more slots. In the example of FIG. 3, the scheduling information **315** may schedule three potential starting positions for an uplink or downlink channel **320**. The UE **115** may perform an LBT procedure for channel access, and the UE **115** may select one or more of the scheduled starting positions based on an outcome of the LBT procedure.

[0119] The grant **310** (e.g., DCI 1_0, or some other grant **310**) may include a TDRA field that supports configuration or allocation of multiple channels **320** having different time domain allocations. For example, the network entity **105** may configure, via a higher layer parameter (e.g., pusch-TimeDomainAllocationListForMultiPUSCH or pusch-TimeDomainAllocationListDCI-0-1), one or more time domain allocations or starting positions, which may be referred to as entries. A quantity of bits in the TDRA field (e.g., between zero and six bits, or some other quantity of bits) may be based on a quantity of entries in the higher layer parameter. For example, a bit width of the TDRA field may be determined by $\lceil \log_2(I) \rceil$ bits, where I may represent a quantity of entries in the higher layer parameter. A value of the TDRA field may thereby indicate one or more of the entries (e.g., starting positions, time domain resource allocations) configured by the higher layer parameter.

[0120] In some cases, as described with reference to FIG. 2, the scheduling information **315** may be transmitted via multiple grants **310** (e.g., configured grants), and each grant **310** may include a respective frequency allocation for a respective channel **320**. If, however, the scheduling information **315** is transmitted via a single grant **310**, such as DCI, for example, the grant **310** may include one FDRA field.

[0121] Techniques described herein provide for configuring, via scheduling information **315** in a single grant **310**, multiple channels **320** each associated with different frequency allocations. For example, an allocation of the channel resources **305** in a frequency domain (e.g., a resource block allocation) may be different in each of the channels **320-a**, **320-b**, and **320-c**. Although the channel resources **305** in each of the channels **320-a**, **320-b**, and **320-c** are illustrated in FIG. 3 as partially overlapping in the frequency domain, it is to be understood that the scheduling information **315** may configure multiple channels **320** having non-overlapping, overlapping, or partially overlapping frequency allocations.

[0122] The grant **310** may include one or more FDRA fields configured to indicate or schedule the multiple different frequency resource allocations. In some aspects, the grant **310** (e.g., DCI, or some other control message) may include multiple FDRA fields each including one or more bits. Each FDRA field may be associated with a respective channel **320** of the multiple channels **320** allocated by the grant **310**. For example, each FDRA field may indicate a respective frequency resource allocation for the respective channel **320**. In the example of FIG. 3, the grant **310** may include a first FDRA field that indicates an allocation of channel resources **305** in the frequency domain for the channel **320-a**, a second FDRA field that indicates an allocation of channel resources **305** in the frequency domain for the channel **320-b**, and a third FDRA field that indicates an allocation of channel resources **305** in the frequency domain for the channel **320-c**. By including multiple FDRA fields in the grant **310**, the scheduling information **315** may thereby allocate multiple channels **320** having the same or different frequency resource allocations.

[0123] In some other aspects, the grant **310** may include a single FDRA field with multiple bits. In such cases, the FDRA field may represent an example of an enhanced FDRA field that may operate similar to a TDRA field, in some aspects. For example, the FDRA field may be configured to accommodate for multiple channels having different quantiles of RBs in the frequency domain. In some aspects, the network entity **105** may transmit a control message (e.g., an RRC message, a MAC-CE, or some other control message) that indicates multiple sets of frequency resources or frequency resource allocations (e.g., a table of frequency resource allocations), and the FDRA field in the grant **310** (e.g., DCI) may indicate a subset of one or more of the sets of frequency resource allocations configured by the control message. For example, a value of the bits in the FDRA field may represent an index to one or more entries in a table of frequency resource allocations. The grant **310** may thereby allocate a different frequency resource allocation for each of the channels **320-a**, **320-b**, and **320-c**.

[0124] A frequency resource allocation for a channel **320** as described herein may include an allocation of a quantity of RBs, a pattern of the RBs in the frequency domain, an offset of the RBs in the frequency domain, or any combination thereof. Each channel **320** scheduled by the scheduling information **315** may be allocated a respective quantity of RBs, a respective pattern of the RBs in the frequency domain, and a respective frequency offset of the RBs. In some aspects, multiple patterns and frequency offsets may be configured via a control message (e.g., RRC or MAC-CE), and the grant **310** (e.g., DCI) may indicate one or more of the multiple patterns and frequency offsets for each channel **320**.

[0125] The UE **115** may use the channel resources **305** indicated by the scheduling information **315** for communications. If the scheduling information schedules multiple downlink channels **320**, the UE **115** may monitor for or receive downlink messages via the scheduled downlink channels **320**. In some aspects, the UE **115** may receive multiple repetitions of a downlink TB via the multiple downlink channels **320**. If the scheduling information **315** schedules multiple uplink channels **320**, the UE **115** may transmit one or more uplink messages (e.g., TBs) via the scheduled uplink channels **320**. If the UE **115** has a single TB to transmit, the UE **115** may perform uplink repetition in one or more of the uplink channels **320** (e.g., to utilize all of the uplink channels **320**). Additionally, or alternatively, in some cases, if the network entity **105** over-allocates the uplink channels **320**, the UE **115** may transmit padding or filler information (e.g., zeros) via one or more

of the allocated uplink channels **320**.

[0126] Techniques described herein provide for the UE **115** to select a subset of uplink channels **320** from the multiple uplink channels **320** allocated by the scheduling information **315** to use for transmissions. For example, the UE **115** may select the channel **320-a** for transmission, and the UE **115** may refrain from transmitting via the channels **320-b** and **320-c**, which may reduce power consumption and overhead. Techniques for uplink channel selection are described in further detail elsewhere herein, including with reference to FIGS. **4-6**.

[0127] FIG. **4** illustrates an example of an uplink channel configuration **400** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The uplink channel configuration **400** may implement or be implemented by aspects of the wireless communications systems **100** and **200** described with reference to FIGS. **1** and **2**. For example, the uplink channel configuration **400** illustrates a configuration of multiple uplink channels **420** for uplink communications between a UE **115** and a network entity **105**, which may represent examples of corresponding devices as described with reference to FIGS. **1-3**. In some aspects, the UE **115** may select a subset or all of the uplink channels **420** allocated for the UE **115**, and the UE **115** may indicate the selection to the network entity **105**.

[0128] The network entity **105** may transmit one or more grants including scheduling information that allocates the multiple uplink channels **420-a**, **420-b**, and **420-c**, as described with reference to FIGS. **2** and **3**. Each uplink channel **420** may be allocated a respective set of uplink channel resources **405** that may be overlapping, partially overlapping, or non-overlapping in the time domain and the frequency domain. For example, the scheduling information may indicate multiple uplink channel resource allocations that may each have a different quantity of RBs in the frequency domain that may be overlapping, partially overlapping, or non-overlapping in time. In some aspects, a quantity of TBs in a buffer at the UE **115** may be transmitted via fewer than all of the allocated uplink channel resources **405**. For example, if the UE **115** has a single TB for transmission, the TB may be transmitted via one of the allocated uplink channels **420**. If the UE **115** transmits repetitions or padding information via the remainder of uplink channels **420**, the UE **115** may utilize unnecessary power or increase overhead.

[0129] As described herein, the UE **115** may select a subset of the uplink channels **420** allocated by the scheduling information and the UE **115** may refrain from transmitting via the remaining uplink channels. For example, if the UE **115** has a single TB for transmission, the UE **115** may select a single grant from among the multiple uplink channel resources **405** (e.g., multi-PUSCH) to use for transmitting the TB.

[0130] The UE **115** may receive an indication that uplink channel selection by the UE **115** is enabled. The UE **115** may receive the indication via the scheduling information or via a control message different than the scheduling information. In some aspects, the indication may be transmitted via a bit in an uplink grant or a type or format of the uplink grant (e.g., an enhanced DCI message for uplink channel selection that may be different than a multi-PUSCH DCI message) may indicate that the uplink channel selection is enabled.

[0131] If the UE **115** is configured for uplink channel selection, the UE **115** may select one or more of the uplink channels **420** allocated by the scheduling information for uplink transmission. The UE **115** may perform the channel selection based on an amount of data in a buffer of the UE **115**, based on one or more channel quality metrics, or both. Each uplink channel **420** may include a respective set of uplink channel resources **405**. In some aspects, the UE **115** may select all of the uplink channel resources **405** in one or more sets (e.g., one or more uplink channels **420**). Additionally, or alternatively, the UE **115** may select a subset of uplink channel resources **405** from one or more sets, as described in further detail elsewhere herein, including with reference to FIG. **5**.

[0132] The network entity **105** may monitor each of the allocated uplink channels **420** for uplink messages from the UE **115**. To alleviate blind detection at the network entity **105** over the grants, the UE **115** as described herein may indicate which uplink channels **420** are selected by the UE **115**

to the network entity **105**. In the example of FIG. **4** the UE **115** may transmit the indication of the selection via one or more common resources **410**, which may correspond to uplink channel resources **405** that are reserved for indicating an uplink channel selection. In some aspects, the common resources **410** may be referred to as reserved resources herein.

[0133] The common resources **410** may include uplink channel resources **405** that are common to (e.g., included within) each of the uplink channels **420** allocated by the scheduling information. The common resources **410** may be present if the uplink channels **420** are at least partially overlapping in the time domain, the frequency domain, or both, as illustrated in FIG. **4**. The UE **115** may autonomously determine or detect the common resources **410** (e.g., RBs) that are common to each of the uplink channels **420** based on the allocation of the uplink channels **420**. Additionally, or alternatively, the network entity **105** may transmit an indication of the common resources **410** to the UE **115** via the scheduling information, the uplink grant, an RRC configuration, a MAC-CE, or any combination thereof.

[0134] The UE **115** may transmit signaling, such as UCI, a DMRS sequence, or both via the common resources **410** to indicate which uplink channel(s) the UE **115** selects. In some aspects, the UE **115** may multiplex UCI over the common resources **410**. The UCI may include an indicator that points to or identifies the uplink channel **420** the UE **115** utilized or selected to transmit a TB. For example, the UCI may include one or more bits configured to indicate an index to the uplink channel **420**.

[0135] In some other aspects, one or more DMRS sequences may be defined on the common resources **410** across the uplink channel allocations, and the UE **115** may utilize one of the DMRS sequences to indicate which uplink channel resources **405** are selected by the UE **115**. A quantity of the DMRS sequences may be the same as a quantity of the uplink channels **420** or sets of uplink channel resources **405**, and each DMRS sequence may map to or identify a respective uplink channel **420** (e.g., K DMRS sequences mapped to K uplink channels **420**).

[0136] In the example of FIG. **4**, the UE **115** may select the uplink channel **420-c** for transmission of a TB. The uplink channel **420-c** may be allocated a respective set of uplink channel resources **405**. The UE **115** may transmit UCI or a DMRS sequence within the common resources **410** that are included in the set of uplink channel resources **405** that are allocated for the uplink channel **420-c** (e.g., via a subset of the set of uplink channel resources **405**) to indicate that the UE **115** selected the uplink channel **420-c**. The network entity **105** may receive the indication and determine to monitor for or perform blind detection in the uplink channel **420-c** and to refrain from monitoring for or performing blind detection in the uplink channels **420-a** and **420-b**.

[0137] Although not illustrated in FIG. **4** for clarity, in some aspects, the scheduling information may allocate a respective sets of reserved resources in each of the uplink channels **420**. For example, a subset of the uplink channel resources **405** in the time domain, the frequency domain, or both, may be reserved for uplink channel selection indication. In such cases, the UE **115** may transmit the UCI, the DMRS sequence, some other reference signal, or any combination thereof via the reserved resources of the selected uplink channel **420** to indicate that the UE **115** selected that uplink channel **420**.

[0138] The UE **115** described herein may thereby select, from among multiple uplink channels **420** allocated by one or more uplink grants, a subset of one or more of the uplink channels **420** for transmission of uplink data. The UE **115** may indicate the selection to a network entity **105** via one or more common resources **410** or reserved resources within the selected uplink channel **420** to reduce blind detection at the network entity **105** and improve reliability and coordination between devices.

[0139] FIG. **5** illustrates an example of an uplink channel configuration **500** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The uplink channel configuration **500** may implement or be implemented by aspects of the wireless communications systems **100** and **200** described with reference to FIGS. **1**

and 2. For example, the uplink channel configuration **500** illustrates a configuration of multiple uplink channels **520** for uplink communications between a UE **115** and a network entity **105**, which may represent examples of corresponding devices as described with reference to FIGS. **1-4**. In some aspects, the UE **115** may select a subset or all of the uplink channels **520** allocated for the UE **115**, and the UE **115** may indicate the selection to the network entity **105**.

[0140] The uplink channel configuration **500** may represent an example of the uplink channel configuration **400** described with reference to FIG. **4**. For example, the multiple uplink channels **520-a**, **520-b**, and **520-c** may include respective sets of uplink channel resources **505** and may be allocated by scheduling information transmitted via one or more uplink grants, as described with reference to FIGS. **2-4**.

[0141] As described with reference to FIG. **4**, the UE **115** may, in some aspects, be configured for uplink channel selection by the UE **115**. In such cases, the UE **115** may select a subset of the uplink channels **520** allocated by the scheduling information and the UE **115** may refrain from transmitting via the remaining uplink channels. For example, if the UE **115** has a single TB for transmission, the UE **115** may select a single grant from among the multiple uplink channel resources **505** (e.g., multi-PUSCH) to use for transmitting the TB. The UE **115** may indicate the uplink channel selection via UCI, DMRS, or both. In some aspects, an amount of data in a buffer at the UE **115** may be transmitted via fewer than all of the uplink channel resources **505** in an allocated uplink channel **520**. Additionally, or alternatively, transmission of uplink data via a subset of the uplink channel resources **505** in one or more uplink channels **520** may improve frequency diversity.

[0142] Techniques described herein provide for the UE **115** to select, from among all of the uplink channel resources **505** allocated by the scheduling information, a subset of uplink channel resources **505** from among a set of uplink channel resources **505** in a given uplink channel **520** to use for uplink transmissions. The selected subset(s) of uplink channel resources **505** may be referred to as and illustrated as selected uplink channel resources **515**. By utilizing different regions (e.g., different RBs) over the different granted uplink channels **520**, the UE **115** may improve frequency diversity, throughput, and reliability of the uplink communications, among other examples.

[0143] In the example of FIG. **5**, the UE **115** may select lower RBs from the first uplink channel **520-a**, the UE **115** may select middle RBs from the second uplink channel **520-b**, and the UE **115** may select upper RBs from the third uplink channel **520-c**. Although the selected uplink channel resources **515** illustrated in FIG. **5** are selected from each of the scheduled uplink channels **520**, it is to be understood that the UE **115** may select a subset of uplink channel resources **505** from a single uplink channel **520**, or any quantity of uplink channels **520**. Additionally, or alternatively, the selected uplink channel resources **515** in each uplink channel **520** may be overlapping, non-overlapping, or partially overlapping in the frequency domain.

[0144] In some aspects, the selected uplink channel resources **515** may be contiguous or noncontiguous in the frequency domain. For example, the selected uplink channel resources **515** in the uplink channel **520-b** may be contiguous to the selected uplink channel resources **515** in the uplink channel **520-a** and noncontiguous to the selected uplink channel resources **515** in the uplink channel **520-c** in the frequency domain. In some aspects (not illustrated in FIG. **5**), the UE **115** may select a first subset of uplink channel resources **505** in a first portion of an uplink channel **520**, and the UE **115** may select a second subset of uplink channel resources **505** in a second portion of the uplink channel **520** that is noncontiguous to the first portion.

[0145] The UE **115** may transmit an indication of the selection via UCI, a DMRS sequence, some other signaling, or any combination thereof. As described with reference to FIG. **4**, the uplink channels **520** may include a set of one or more reserved resources **510** for transmitting the channel selection indication. If the uplink channels **520** are at least partially overlapping in time and frequency, the reserved resources **510** may include resources that are common to (e.g., included

within) each of the uplink channels **520**, as illustrated in FIG. 5. Additionally, or alternatively, the scheduling information may allocate a set of reserved resources **510** in each uplink channel **520**. The UE **115** may transmit (e.g., multiplex) the UCI, a DMRS, or both via the reserved resources **510** that are within the selected channel **520**.

[0146] In the example of FIG. 5, the UCI may include one or more bits or fields configured to indicate which uplink channel resources **505** are selected uplink channel resources **515**. For example, one or more bits in the UCI may indicate whether the UE **115** selects all of an allocated uplink channel **520** or a portion of an allocated uplink channel **520**. If the UE **115** selects a portion (e.g., a subset of resources), one or more bits in the UCI may provide a bitmap to indicate the selected uplink channel resources **515**. For example, each subset of uplink channel resources **505** may be indexed by a respective value of the bitmap. The fields or bits in the UCI that are used to indicate a selected uplink channel **520** may be the same as or different than the fields or bits in the UCI that are used to indicate a portion of selected uplink channel resources **515**.

[0147] The UE **115** may thereby select a portion of an allocated uplink channel **520** to use for uplink transmissions. The UE **115** may transmit one or more TBs via the selected uplink channel resources **515** and the UE **115** may refrain from transmitting via other uplink channel resources **505** that are not selected to reduce power consumption and overhead. The UE **115** may indicate the selected uplink channel resources **515** to a network entity **105** via UCI, a DMRS, or both to reduce blind detection and processing at the network entity **105**.

[0148] FIG. 6 illustrates an example of an uplink channel configuration **600** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The uplink channel configuration **600** may implement or be implemented by aspects of the wireless communications systems **100** and **200** described with reference to FIGS. 1 and 2. For example, the uplink channel configuration **600** illustrates a configuration of multiple uplink channels **620** for uplink communications between a UE **115** and a network entity **105**, which may represent examples of corresponding devices as described with reference to FIGS. 1-5. In some aspects, the UE **115** may select a subset or all of the uplink channels **620** allocated for the UE **115**, and the UE **115** may indicate the selection to the network entity **105**.

[0149] The uplink channel configuration **600** may represent an example of the uplink channel configuration **400** and the uplink channel configuration **500** described with reference to FIGS. 4 and 5. For example, the multiple uplink channels **620-a**, **620-b**, and **620-c** may include respective sets of uplink channel resources **605** and may be allocated by scheduling information transmitted via one or more uplink grants, as described with reference to FIGS. 2-5. The UE **115** may be configured to support uplink channel selection, and the UE **115** may select one or more of the uplink channels **620**, a subset of uplink channel resources **605** within one or more of the uplink channels **620**, or both, to use for transmission of one or more uplink TBs. As described with reference to FIGS. 2-5, the UE **115** may indicate which uplink channels **620** or portions of uplink channels **620** are selected to the network entity **105** to reduce blind detection.

[0150] In some aspects described herein, the UE **115** may utilize one or more DMRS sequences **610** configured to indicate the uplink channel selection. For example, each uplink channel **620** may be configured with or associated with a respective DMRS sequence **610**. The DMRS sequences **610** may be configured or indicated via the scheduling information or a control message different than the scheduling information (e.g., RRC, MAC-CE). The DMRS sequences **610** may be concatenated or appended to a front of the uplink channel **620** in the time domain (e.g., a front-loaded sequence). The DMRS sequence may be transmitted via resources that span across all or a portion of RBs allocated for the respective uplink channel **620** in the frequency domain.

[0151] If the UE **115** selects all or a portion of an uplink channel **620**, the UE **115** may transmit an uplink TB via the selected uplink channel **620**, and the UE **115** may transmit the DMRS sequence **610** associated with the selected uplink channel **620**. The front-loaded DMRS sequence **610** may indicate, to the network entity **105**, that the UE **115** selected the corresponding uplink channel **620**,

which may provide for early detection of the utilized uplink channel **620**. In the example of FIG. **6**, the UE **115** may select the uplink channel resources **605** in the uplink channel **620-c**, and the UE **115** may transmit the DMRS sequence **610** via a first portion of the uplink channel resources **605** in the uplink channel **620-c** to indicate the selection. The UE **115** may refrain from transmitting via at least a portion of the uplink channels **620-a** and **620-b** based on the selection. For example, the UE **115** may refrain from transmitting via uplink channel resources **605** in the uplink channels **620-a** and **620-b** that are non-overlapping with the uplink channel resources **605** in the selected uplink channel **620-c**.

[0152] In some aspects, the UE **115** may select a portion of an uplink channel **620-c**. For example, the UE **115** may select a subset of uplink channel resources **605** from within one or more of the scheduled uplink channels **620**, as described and illustrated with reference to FIG. **5**. The UE **115** may, in some aspects, still transmit a corresponding DMRS sequence **610** to indicate the selected uplink channel resources **605**. For example, the DMRS sequence **610** may indicate that the network entity **105** is to monitor at least some uplink channel resources **605** in the corresponding uplink channel **620**. Additionally, or alternatively, the DMRS sequence **610** may include one or more fields or bits configured to indicate the selected subset of uplink channel resources **605** within the uplink channel **620**.

[0153] The UE **115** may transmit one or more TBs via the selected uplink channel resources **605**. The UE **115** may thereby select a subset of allocated uplink channel resources **605** to use for an uplink transmission and may indicate the selection to a network entity **105** via a DMRS sequence **610**, which may reduce power consumption, overhead, and processing at both the network entity **105** and the UE **115**.

[0154] FIG. **7** illustrates an example of a process flow **700** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The process flow **700** may implement or be implemented by aspects of the wireless communications systems **100** and **200**, the channel configuration scheme **300**, or the uplink channel configurations **400**, **500**, and **600** described with reference to FIGS. **1-6**. For example, the process flow **700** illustrates communications between a UE **115-b** and a network entity **105-b**, which may represent examples of corresponding devices as described with reference to FIGS. **1-6**.

[0155] In the following description of the process flow **700**, the operations between the UE **115-b** and the network entity **105-b** may be performed in different orders or at different times. Some operations may also be left out of the process flow **700**, or other operations may be added. Although the UE **115-b** and the network entity **105-b** are shown performing the operations of the process flow **700**, some aspects of some operations may also be performed by one or more other wireless devices.

[0156] At **705**, the network entity **105-b** may transmit scheduling information to the UE **115-b**. The scheduling information may allocate multiple uplink channels of a same channel type to the UE **115-b**. In some aspects, each uplink channel may correspond to or be allocated by a set of uplink channel resources (e.g., PUSCH resources). The scheduling information may indicate a respective set of frequency resources for each of the uplink channels. That is, each uplink channel may be scheduled with a respective set of frequency resources that may be fully, partially, or non-overlapping in a frequency domain. The scheduling information may be transmitted via DCI, a MAC-CE, an RRC message, some other control signaling, or any combination thereof.

[0157] At **710**, in some aspects, the network entity **105-b** may transmit, to the UE **115-b**, an indication that uplink channel selection by the UE **115-b** is enabled for the multiple uplink channels allocated via the scheduling information. In some aspects, the indication may be transmitted via a control message that is different than the scheduling information. Additionally, or alternatively, the indication may be transmitted via the scheduling information. For example, if the scheduling information includes DCI, the indication may be transmitted via a bit in the DCI, or a format of the DCI may indicate that uplink channel selection is enabled by the UE **115-b**.

[0158] At **715**, the UE **115-b** may select, from among the multiple uplink channels allocated via the scheduling information, at least a portion of a first uplink channel that includes a first set of frequency resources. The UE **115-b** may select the first uplink channel based on a quantity of data in a buffer at the UE **115-b**, based on one or more communications parameters (e.g., a channel quality), based on a power level of the UE **115-b**, or any combination thereof.

[0159] At **720**, the UE **115-b** may transmit an uplink message to the network entity **105-b** via the first uplink channel based on selecting the first uplink channel. In some aspects, the UE **115-b** may transmit, via at least a portion of the first set of frequency resources in the first uplink channel, an indication that the UE **115-b** selected the first uplink channel. The indication may be transmitted via UCI, a DMRS, or some other signaling, as described with reference to FIGS. **4-6**.

[0160] At **725**, based on selecting the first uplink channel, the UE **115-b** may refrain from transmitting via the other uplink channels allocated via the scheduling information (or, for each of the other uplink channels, refrain from transmitting via at least a portion of the other uplink channel). The second uplink channel may be associated with a second set of frequency resources. That is, the UE **115-b** may select fewer than all of the uplink channels allocated via the scheduling information, and the UE **115-b** may refrain from transmitting on the remaining unselected channels, which may reduce overhead and power consumption by the UE **115-b**.

[0161] FIG. **8** shows a block diagram **800** of a device **805** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The device **805** may be an example of aspects of a UE **115** as described herein. The device **805** may include a receiver **810**, a transmitter **815**, and a communications manager **820**. The device **805** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

[0162] The receiver **810** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to frequency resource selection for multiple channels). Information may be passed on to other components of the device **805**. The receiver **810** may utilize a single antenna or a set of multiple antennas.

[0163] The transmitter **815** may provide a means for transmitting signals generated by other components of the device **805**. For example, the transmitter **815** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to frequency resource selection for multiple channels). In some examples, the transmitter **815** may be co-located with a receiver **810** in a transceiver module. The transmitter **815** may utilize a single antenna or a set of multiple antennas.

[0164] The communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations thereof or various components thereof may be examples of means for performing various aspects of frequency resource selection for multiple channels as described herein. For example, the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may support a method for performing one or more of the functions described herein.

[0165] In some examples, the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be implemented in hardware (e.g., in communications management circuitry). The hardware may include a processor, a digital signal processor (DSP), a central processing unit (CPU), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA) or other programmable logic device, a microcontroller, discrete gate or transistor logic, discrete hardware components, or any combination thereof configured as or otherwise supporting a means for performing the functions described in the present disclosure. In some examples, a processor and memory coupled with the processor may be configured to perform one or more of the functions described herein (e.g., by executing, by the

processor, instructions stored in the memory).

[0166] Additionally, or alternatively, in some examples, the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be implemented in code (e.g., as communications management software or firmware) executed by a processor. If implemented in code executed by a processor, the functions of the communications manager **820**, the receiver **810**, the transmitter **815**, or various combinations or components thereof may be performed by a general-purpose processor, a DSP, a CPU, an ASIC, an FPGA, a microcontroller, or any combination of these or other programmable logic devices (e.g., configured as or otherwise supporting a means for performing the functions described in the present disclosure).

[0167] In some examples, the communications manager **820** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **810**, the transmitter **815**, or both. For example, the communications manager **820** may receive information from the receiver **810**, send information to the transmitter **815**, or be integrated in combination with the receiver **810**, the transmitter **815**, or both to obtain information, output information, or perform various other operations as described herein.

[0168] The communications manager **820** may support wireless communication at a UE in accordance with examples as disclosed herein. For example, the communications manager **820** may be configured as or otherwise support a means for receiving scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels. The communications manager **820** may be configured as or otherwise support a means for selecting, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources. The communications manager **820** may be configured as or otherwise support a means for transmitting an uplink message via the first uplink channel based on the selecting. The communications manager **820** may be configured as or otherwise support a means for refraining from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources.

[0169] By including or configuring the communications manager **820** in accordance with examples as described herein, the device **805** (e.g., a processor controlling or otherwise coupled with the receiver **810**, the transmitter **815**, the communications manager **820**, or a combination thereof) may support techniques for reduced processing, reduced power consumption, and more efficient utilization of communication resources, among other advantages. For example, by selecting a subset of uplink channels from among a set of multiple uplink channels allocated via scheduling information, a processor of the device **805** (e.g., a UE **115**) may refrain from excessive transmissions via overallocated resources, which may reduce processing and power consumption and may reduce overhead. In some aspects, the remaining unselected resources may be used for other communications, or may be null, which may reduce interference with other communications, thereby improving utilization of communication resources and communication reliability.

[0170] FIG. **9** shows a block diagram **900** of a device **905** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The device **905** may be an example of aspects of a device **805** or a UE **115** as described herein. The device **905** may include a receiver **910**, a transmitter **915**, and a communications manager **920**. The device **905** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

[0171] The receiver **910** may provide a means for receiving information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to frequency resource selection for multiple channels). Information may be passed on to other components of the device **905**. The

receiver **910** may utilize a single antenna or a set of multiple antennas.

[0172] The transmitter **915** may provide a means for transmitting signals generated by other components of the device **905**. For example, the transmitter **915** may transmit information such as packets, user data, control information, or any combination thereof associated with various information channels (e.g., control channels, data channels, information channels related to frequency resource selection for multiple channels). In some examples, the transmitter **915** may be co-located with a receiver **910** in a transceiver module. The transmitter **915** may utilize a single antenna or a set of multiple antennas.

[0173] The device **905**, or various components thereof, may be an example of means for performing various aspects of frequency resource selection for multiple channels as described herein. For example, the communications manager **920** may include a scheduling information component **925**, an uplink channel selection component **930**, an uplink message component **935**, or any combination thereof. The communications manager **920** may be an example of aspects of a communications manager **820** as described herein. In some examples, the communications manager **920**, or various components thereof, may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **910**, the transmitter **915**, or both. For example, the communications manager **920** may receive information from the receiver **910**, send information to the transmitter **915**, or be integrated in combination with the receiver **910**, the transmitter **915**, or both to obtain information, output information, or perform various other operations as described herein.

[0174] The communications manager **920** may support wireless communication at a UE in accordance with examples as disclosed herein. The scheduling information component **925** may be configured as or otherwise support a means for receiving scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels. The uplink channel selection component **930** may be configured as or otherwise support a means for selecting, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources. The uplink message component **935** may be configured as or otherwise support a means for transmitting an uplink message via the first uplink channel based on the selecting. The uplink message component **935** may be configured as or otherwise support a means for refraining from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources.

[0175] FIG. **10** shows a block diagram **1000** of a communications manager **1020** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The communications manager **1020** may be an example of aspects of a communications manager **820**, a communications manager **920**, or both, as described herein. The communications manager **1020**, or various components thereof, may be an example of means for performing various aspects of frequency resource selection for multiple channels as described herein. For example, the communications manager **1020** may include a scheduling information component **1025**, an uplink channel selection component **1030**, an uplink message component **1035**, a UCI component **1040**, a DMRS component **1045**, a reserved resource component **1050**, a frequency allocation component **1055**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses).

[0176] The communications manager **1020** may support wireless communication at a UE in accordance with examples as disclosed herein. The scheduling information component **1025** may be configured as or otherwise support a means for receiving scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels. The uplink channel selection component **1030** may be configured as or otherwise support a means for

selecting, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources. The uplink message component **1035** may be configured as or otherwise support a means for transmitting an uplink message via the first uplink channel based on the selecting. In some examples, the uplink message component **1035** may be configured as or otherwise support a means for refraining from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources.

[0177] In some examples, to support receiving the scheduling information, the uplink channel selection component **1030** may be configured as or otherwise support a means for receiving, via the scheduling information, an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels, where the UE selecting the first uplink channel may be based on the indication that uplink channel selection is enabled. In some examples, the scheduling information includes a DCI message. In some examples, the indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels includes a format of the DCI message.

[0178] In some examples, the set of multiple uplink channels are at least partially overlapping in a frequency domain, and the UCI component **1040** may be configured as or otherwise support a means for transmitting, within a subset of the first set of frequency resources that is common to the set of multiple uplink channels, UCI that indicates that the UE has selected the first uplink channel from among the set of multiple uplink channels.

[0179] In some examples, the UCI component **1040** may be configured as or otherwise support a means for selecting a second subset of the first set of frequency resources for transmitting the uplink message, where the uplink message may be transmitted within the second subset of the first set of frequency resources, and where the UCI may further indicate that the UE has selected the second subset for transmitting the uplink message.

[0180] In some examples, the reserved resource component **1050** may be configured as or otherwise support a means for receiving, via the scheduling information or a control message that is different than the scheduling information, an indication of the subset of the first set of frequency resources that is common to the set of multiple uplink channels.

[0181] In some examples, the set of multiple uplink channels are at least partially overlapping in a frequency domain, and the DMRS component **1045** may be configured as or otherwise support a means for transmitting, via a subset of the first set of frequency resources, a DMRS sequence that indicates that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the subset of the first set of frequency resources is common to the set of multiple uplink channels.

[0182] In some examples, each of the set of multiple uplink channels includes a respective set of reserved resources for UCI, and the reserved resource component **1050** may be configured as or otherwise support a means for transmitting, via the respective set of reserved resources within the first uplink channel, UCI that indicates that the UE has selected the first uplink channel from among the set of multiple uplink channels.

[0183] In some examples, each of the set of multiple uplink channels is associated with a respective DMRS sequence, and the DMRS component **1045** may be configured as or otherwise support a means for transmitting, via a portion of the first uplink channel, the respective DMRS sequence for the first uplink channel to indicate that the UE has selected the first uplink channel from among the set of multiple uplink channels.

[0184] In some examples, to support receiving the scheduling information, the frequency allocation component **1055** may be configured as or otherwise support a means for receiving, within the scheduling information, a set of multiple FDRA fields that each allocate a respective uplink channel of the set of multiple uplink channels.

[0185] In some examples, the frequency allocation component **1055** may be configured as or otherwise support a means for receiving a control message that indicates a set of multiple sets of

frequency resources, where an FDRA field within the scheduling information indicates a subset of the set of multiple sets of frequency resources, the subset including the respective sets of frequency resources for the set of multiple uplink channels.

[0186] In some examples, to support receiving the scheduling information, the scheduling information component **1025** may be configured as or otherwise support a means for receiving a DCI message that allocates the set of multiple uplink channels to the UE and indicates the respective sets of frequency resources for the set of multiple uplink channels.

[0187] In some examples, to support receiving the scheduling information, the scheduling information component **1025** may be configured as or otherwise support a means for receiving at least one configured grant that allocates the set of multiple uplink channels to the UE and indicates the respective sets of frequency resources for the set of multiple uplink channels.

[0188] In some examples, the set of multiple uplink channels allocated to the UE may be overlapping in a time domain. In some examples, the set of multiple uplink channels allocated to the UE may be partially overlapping or non-overlapping in a frequency domain.

[0189] FIG. **11** shows a diagram of a system **1100** including a device **1105** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The device **1105** may be an example of or include the components of a device **805**, a device **905**, or a UE **115** as described herein. The device **1105** may communicate (e.g., wirelessly) with one or more network entities **105**, one or more UEs **115**, or any combination thereof. The device **1105** may include components for bi-directional voice and data communications including components for transmitting and receiving communications, such as a communications manager **1120**, an input/output (I/O) controller **1110**, a transceiver **1115**, an antenna **1125**, a memory **1130**, code **1135**, and a processor **1140**. These components may be in electronic communication or otherwise coupled (e.g., operatively, communicatively, functionally, electronically, electrically) via one or more buses (e.g., a bus **1145**).

[0190] The I/O controller **1110** may manage input and output signals for the device **1105**. The I/O controller **1110** may also manage peripherals not integrated into the device **1105**. In some cases, the I/O controller **1110** may represent a physical connection or port to an external peripheral. In some cases, the I/O controller **1110** may utilize an operating system such as iOS®, ANDROID®, MS-DOS®, MS-WINDOWS®, OS/2®, UNIX®, LINUX®, or another known operating system. Additionally, or alternatively, the I/O controller **1110** may represent or interact with a modem, a keyboard, a mouse, a touchscreen, or a similar device. In some cases, the I/O controller **1110** may be implemented as part of a processor, such as the processor **1140**. In some cases, a user may interact with the device **1105** via the I/O controller **1110** or via hardware components controlled by the I/O controller **1110**.

[0191] In some cases, the device **1105** may include a single antenna **1125**. However, in some other cases, the device **1105** may have more than one antenna **1125**, which may be capable of concurrently transmitting or receiving multiple wireless transmissions. The transceiver **1115** may communicate bi-directionally, via the one or more antennas **1125**, wired, or wireless links as described herein. For example, the transceiver **1115** may represent a wireless transceiver and may communicate bi-directionally with another wireless transceiver. The transceiver **1115** may also include a modem to modulate the packets, to provide the modulated packets to one or more antennas **1125** for transmission, and to demodulate packets received from the one or more antennas **1125**. The transceiver **1115**, or the transceiver **1115** and one or more antennas **1125**, may be an example of a transmitter **815**, a transmitter **915**, a receiver **810**, a receiver **910**, or any combination thereof or component thereof, as described herein.

[0192] The memory **1130** may include random access memory (RAM) and read-only memory (ROM). The memory **1130** may store computer-readable, computer-executable code **1135** including instructions that, when executed by the processor **1140**, cause the device **1105** to perform various functions described herein. The code **1135** may be stored in a non-transitory computer-readable

medium such as system memory or another type of memory. In some cases, the code **1135** may not be directly executable by the processor **1140** but may cause a computer (e.g., when compiled and executed) to perform functions described herein. In some cases, the memory **1130** may contain, among other things, a basic I/O system (BIOS) which may control basic hardware or software operation such as the interaction with peripheral components or devices.

[0193] The processor **1140** may include an intelligent hardware device (e.g., a general-purpose processor, a DSP, a CPU, a microcontroller, an ASIC, an FPGA, a programmable logic device, a discrete gate or transistor logic component, a discrete hardware component, or any combination thereof). In some cases, the processor **1140** may be configured to operate a memory array using a memory controller. In some other cases, a memory controller may be integrated into the processor **1140**. The processor **1140** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **1130**) to cause the device **1105** to perform various functions (e.g., functions or tasks supporting frequency resource selection for multiple channels). For example, the device **1105** or a component of the device **1105** may include a processor **1140** and memory **1130** coupled with or to the processor **1140**, the processor **1140** and memory **1130** configured to perform various functions described herein.

[0194] The communications manager **1120** may support wireless communication at a UE in accordance with examples as disclosed herein. For example, the communications manager **1120** may be configured as or otherwise support a means for receiving scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels. The communications manager **1120** may be configured as or otherwise support a means for selecting, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources. The communications manager **1120** may be configured as or otherwise support a means for transmitting an uplink message via the first uplink channel based on the selecting. The communications manager **1120** may be configured as or otherwise support a means for refraining from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources.

[0195] By including or configuring the communications manager **1120** in accordance with examples as described herein, the device **1105** may support techniques for improved communication reliability, reduced latency, improved user experience related to reduced processing, reduced power consumption, more efficient utilization of communication resources, improved coordination between devices, and longer battery life, among other advantages.

[0196] In some examples, the communications manager **1120** may be configured to perform various operations (e.g., receiving, monitoring, transmitting) using or otherwise in cooperation with the transceiver **1115**, the one or more antennas **1125**, or any combination thereof. For example, the communications manager **1120** may be configured to receive or transmit messages or other signaling as described herein via the transceiver **1115**. Although the communications manager **1120** is illustrated as a separate component, in some examples, one or more functions described with reference to the communications manager **1120** may be supported by or performed by the processor **1140**, the memory **1130**, the code **1135**, or any combination thereof. For example, the code **1135** may include instructions executable by the processor **1140** to cause the device **1105** to perform various aspects of frequency resource selection for multiple channels as described herein, or the processor **1140** and the memory **1130** may be otherwise configured to perform or support such operations.

[0197] FIG. 12 shows a block diagram **1200** of a device **1205** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The device **1205** may be an example of aspects of a network entity **105** as described herein. The device **1205** may include a receiver **1210**, a transmitter **1215**, and a communications manager **1220**.

The device **1205** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

[0198] The receiver **1210** may provide a means for obtaining (e.g., receiving, determining, identifying) information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). Information may be passed on to other components of the device **1205**. In some examples, the receiver **1210** may support obtaining information by receiving signals via one or more antennas. Additionally, or alternatively, the receiver **1210** may support obtaining information by receiving signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof.

[0199] The transmitter **1215** may provide a means for outputting (e.g., transmitting, providing, conveying, sending) information generated by other components of the device **1205**. For example, the transmitter **1215** may output information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). In some examples, the transmitter **1215** may support outputting information by transmitting signals via one or more antennas. Additionally, or alternatively, the transmitter **1215** may support outputting information by transmitting signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof. In some examples, the transmitter **1215** and the receiver **1210** may be co-located in a transceiver, which may include or be coupled with a modem.

[0200] The communications manager **1220**, the receiver **1210**, the transmitter **1215**, or various combinations thereof or various components thereof may be examples of means for performing various aspects of frequency resource selection for multiple channels as described herein. For example, the communications manager **1220**, the receiver **1210**, the transmitter **1215**, or various combinations or components thereof may support a method for performing one or more of the functions described herein.

[0201] In some examples, the communications manager **1220**, the receiver **1210**, the transmitter **1215**, or various combinations or components thereof may be implemented in hardware (e.g., in communications management circuitry). The hardware may include a processor, a DSP, a CPU, an ASIC, an FPGA or other programmable logic device, a microcontroller, discrete gate or transistor logic, discrete hardware components, or any combination thereof configured as or otherwise supporting a means for performing the functions described in the present disclosure. In some examples, a processor and memory coupled with the processor may be configured to perform one or more of the functions described herein (e.g., by executing, by the processor, instructions stored in the memory).

[0202] Additionally, or alternatively, in some examples, the communications manager **1220**, the receiver **1210**, the transmitter **1215**, or various combinations or components thereof may be implemented in code (e.g., as communications management software or firmware) executed by a processor. If implemented in code executed by a processor, the functions of the communications manager **1220**, the receiver **1210**, the transmitter **1215**, or various combinations or components thereof may be performed by a general-purpose processor, a DSP, a CPU, an ASIC, an FPGA, a microcontroller, or any combination of these or other programmable logic devices (e.g., configured as or otherwise supporting a means for performing the functions described in the present disclosure).

[0203] In some examples, the communications manager **1220** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **1210**, the transmitter **1215**, or both. For example, the communications manager **1220** may receive information from the receiver **1210**, send information

to the transmitter **1215**, or be integrated in combination with the receiver **1210**, the transmitter **1215**, or both to obtain information, output information, or perform various other operations as described herein.

[0204] The communications manager **1220** may support wireless communication at a network entity in accordance with examples as disclosed herein. For example, the communications manager **1220** may be configured as or otherwise support a means for transmitting scheduling information that allocates a set of multiple uplink channels of a same channel type to a UE, where the scheduling information may indicate respective sets of frequency resources for the set of multiple uplink channels. The communications manager **1220** may be configured as or otherwise support a means for transmitting an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels. The communications manager **1220** may be configured as or otherwise support a means for receiving an uplink message via a first uplink channel based on identifying that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the first uplink channel includes a first set of frequency resources.

[0205] By including or configuring the communications manager **1220** in accordance with examples as described herein, the device **1205** (e.g., a processor controlling or otherwise coupled with the receiver **1210**, the transmitter **1215**, the communications manager **1220**, or a combination thereof) may support techniques for reduced processing, reduced power consumption, and more efficient utilization of communication resources.

[0206] FIG. **13** shows a block diagram **1300** of a device **1305** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The device **1305** may be an example of aspects of a device **1205** or a network entity **105** as described herein. The device **1305** may include a receiver **1310**, a transmitter **1315**, and a communications manager **1320**. The device **1305** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

[0207] The receiver **1310** may provide a means for obtaining (e.g., receiving, determining, identifying) information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). Information may be passed on to other components of the device **1305**. In some examples, the receiver **1310** may support obtaining information by receiving signals via one or more antennas. Additionally, or alternatively, the receiver **1310** may support obtaining information by receiving signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof.

[0208] The transmitter **1315** may provide a means for outputting (e.g., transmitting, providing, conveying, sending) information generated by other components of the device **1305**. For example, the transmitter **1315** may output information such as user data, control information, or any combination thereof (e.g., I/Q samples, symbols, packets, protocol data units, service data units) associated with various channels (e.g., control channels, data channels, information channels, channels associated with a protocol stack). In some examples, the transmitter **1315** may support outputting information by transmitting signals via one or more antennas. Additionally, or alternatively, the transmitter **1315** may support outputting information by transmitting signals via one or more wired (e.g., electrical, fiber optic) interfaces, wireless interfaces, or any combination thereof. In some examples, the transmitter **1315** and the receiver **1310** may be co-located in a transceiver, which may include or be coupled with a modem.

[0209] The device **1305**, or various components thereof, may be an example of means for performing various aspects of frequency resource selection for multiple channels as described herein. For example, the communications manager **1320** may include a scheduling information component **1325**, an uplink channel selection component **1330**, an uplink message component **1335**, or any combination thereof. The communications manager **1320** may be an example of

aspects of a communications manager **1220** as described herein. In some examples, the communications manager **1320**, or various components thereof, may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the receiver **1310**, the transmitter **1315**, or both. For example, the communications manager **1320** may receive information from the receiver **1310**, send information to the transmitter **1315**, or be integrated in combination with the receiver **1310**, the transmitter **1315**, or both to obtain information, output information, or perform various other operations as described herein.

[0210] The communications manager **1320** may support wireless communication at a network entity in accordance with examples as disclosed herein. The scheduling information component **1325** may be configured as or otherwise support a means for transmitting scheduling information that allocates a set of multiple uplink channels of a same channel type to a UE, where the scheduling information may indicate respective sets of frequency resources for the set of multiple uplink channels. The uplink channel selection component **1330** may be configured as or otherwise support a means for transmitting an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels. The uplink message component **1335** may be configured as or otherwise support a means for receiving an uplink message via a first uplink channel based on identifying that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the first uplink channel includes a first set of frequency resources.

[0211] FIG. **14** shows a block diagram **1400** of a communications manager **1420** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The communications manager **1420** may be an example of aspects of a communications manager **1220**, a communications manager **1320**, or both, as described herein. The communications manager **1420**, or various components thereof, may be an example of means for performing various aspects of frequency resource selection for multiple channels as described herein. For example, the communications manager **1420** may include a scheduling information component **1425**, an uplink channel selection component **1430**, an uplink message component **1435**, a reserved resource component **1440**, a UCI component **1445**, a DMRS component **1450**, a frequency allocation component **1455**, or any combination thereof. Each of these components may communicate, directly or indirectly, with one another (e.g., via one or more buses) which may include communications within a protocol layer of a protocol stack, communications associated with a logical channel of a protocol stack (e.g., between protocol layers of a protocol stack, within a device, component, or virtualized component associated with a network entity **105**, between devices, components, or virtualized components associated with a network entity **105**), or any combination thereof.

[0212] The communications manager **1420** may support wireless communication at a network entity in accordance with examples as disclosed herein. The scheduling information component **1425** may be configured as or otherwise support a means for transmitting scheduling information that allocates a set of multiple uplink channels of a same channel type to a UE, where the scheduling information may indicate respective sets of frequency resources for the set of multiple uplink channels. The uplink channel selection component **1430** may be configured as or otherwise support a means for transmitting an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels. The uplink message component **1435** may be configured as or otherwise support a means for receiving an uplink message via a first uplink channel based on identifying that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the first uplink channel includes a first set of frequency resources.

[0213] In some examples, to support transmitting the scheduling information, the uplink channel selection component **1430** may be configured as or otherwise support a means for transmitting, within the scheduling information, the indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels.

[0214] In some examples, the set of multiple uplink channels are at least partially overlapping in a frequency domain, and the reserved resource component **1440** may be configured as or otherwise support a means for transmitting, via the scheduling information or a control message that is different than the scheduling information, an indication of a subset of the first set of frequency resources that is common to the set of multiple uplink channels. In some examples, the set of multiple uplink channels are at least partially overlapping in a frequency domain, and the uplink channel selection component **1430** may be configured as or otherwise support a means for receiving, via the subset of the first set of frequency resources, an indication that the UE has selected, from among the set of multiple uplink channels, at least a portion of the first set of frequency resources in the first uplink channel for transmitting the uplink message, where identifying that the UE has selected the first uplink channel may be based upon receiving the indication.

[0215] In some examples, each of the set of multiple uplink channels includes a respective set of reserved resources for uplink control information, and the UCI component **1445** may be configured as or otherwise support a means for receiving, via the respective set of reserved resources within the first uplink channel, UCI that indicates that the UE selected the first uplink channel from among the set of multiple uplink channels, where identifying that the UE has selected the first uplink channel is based upon receiving the indication.

[0216] In some examples, each of the set of multiple uplink channels is associated with a respective DMRS sequence, and the DMRS component **1450** may be configured as or otherwise support a means for receiving, via a portion of the first uplink channel, the respective DMRS sequence for the first uplink channel, where identifying that the UE selected the first uplink channel may be based on receiving the respective DMRS sequence for the first uplink channel.

[0217] In some examples, to support transmitting the scheduling information, the frequency allocation component **1455** may be configured as or otherwise support a means for transmitting, within the scheduling information, a set of multiple FDRA fields that each allocate a respective uplink channel of the set of multiple uplink channels.

[0218] In some examples, the frequency allocation component **1455** may be configured as or otherwise support a means for transmitting a control message that indicates a set of multiple sets of frequency resources, where an FDRA field within the scheduling information indicates a subset of the set of multiple sets of frequency resources, the subset including the respective sets of frequency resources for the set of multiple uplink channels.

[0219] In some examples, to support transmitting the scheduling information, the scheduling information component **1425** may be configured as or otherwise support a means for transmitting a DCI message or at least one configured grant that allocates the set of multiple uplink channels to the UE and indicates the respective sets of frequency resources for the set of multiple uplink channels.

[0220] In some examples, no signaling may be received from the UE within at least a portion of a second uplink channel of the set of multiple uplink channels, the second uplink channel including a second set of frequency resources set. In some examples, the set of multiple uplink channels allocated to the UE are overlapping in a time domain. In some examples, the set of multiple uplink channels allocated to the UE are partially overlapping or non-overlapping in a frequency domain.

[0221] FIG. 15 shows a diagram of a system **1500** including a device **1505** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The device **1505** may be an example of or include the components of a device **1205**, a device **1305**, or a network entity **105** as described herein. The device **1505** may communicate with one or more network entities **105**, one or more UEs **115**, or any combination thereof, which may include communications over one or more wired interfaces, over one or more wireless interfaces, or any combination thereof. The device **1505** may include components that support outputting and obtaining communications, such as a communications manager **1520**, a transceiver **1510**, an

antenna **1515**, a memory **1525**, code **1530**, and a processor **1535**. These components may be in electronic communication or otherwise coupled (e.g., operatively, communicatively, functionally, electronically, electrically) via one or more buses (e.g., a bus **1540**).

[0222] The transceiver **1510** may support bi-directional communications via wired links, wireless links, or both as described herein. In some examples, the transceiver **1510** may include a wired transceiver and may communicate bi-directionally with another wired transceiver. Additionally, or alternatively, in some examples, the transceiver **1510** may include a wireless transceiver and may communicate bi-directionally with another wireless transceiver. In some examples, the device **1505** may include one or more antennas **1515**, which may be capable of transmitting or receiving wireless transmissions (e.g., concurrently). The transceiver **1510** may also include a modem to modulate signals, to provide the modulated signals for transmission (e.g., by one or more antennas **1515**, by a wired transmitter), to receive modulated signals (e.g., from one or more antennas **1515**, from a wired receiver), and to demodulate signals. In some implementations, the transceiver **1510** may include one or more interfaces, such as one or more interfaces coupled with the one or more antennas **1515** that are configured to support various receiving or obtaining operations, or one or more interfaces coupled with the one or more antennas **1515** that are configured to support various transmitting or outputting operations, or a combination thereof. In some implementations, the transceiver **1510** may include or be configured for coupling with one or more processors or memory components that are operable to perform or support operations based on received or obtained information or signals, or to generate information or other signals for transmission or other outputting, or any combination thereof. In some implementations, the transceiver **1510**, or the transceiver **1510** and the one or more antennas **1515**, or the transceiver **1510** and the one or more antennas **1515** and one or more processors or memory components (for example, the processor **1535**, or the memory **1525**, or both), may be included in a chip or chip assembly that is installed in the device **1505**. The transceiver **1510**, or the transceiver **1510** and one or more antennas **1515** or wired interfaces, where applicable, may be an example of a transmitter **1215**, a transmitter **1315**, a receiver **1210**, a receiver **1310**, or any combination thereof or component thereof, as described herein. In some examples, the transceiver may be operable to support communications via one or more communications links (e.g., a communication link **125**, a backhaul communication link **120**, a midhaul communication link **162**, a fronthaul communication link **168**).

[0223] The memory **1525** may include RAM and ROM. The memory **1525** may store computer-readable, computer-executable code **1530** including instructions that, when executed by the processor **1535**, cause the device **1505** to perform various functions described herein. The code **1530** may be stored in a non-transitory computer-readable medium such as system memory or another type of memory. In some cases, the code **1530** may not be directly executable by the processor **1535** but may cause a computer (e.g., when compiled and executed) to perform functions described herein. In some cases, the memory **1525** may contain, among other things, a BIOS which may control basic hardware or software operation such as the interaction with peripheral components or devices.

[0224] The processor **1535** may include an intelligent hardware device (e.g., a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA, a microcontroller, a programmable logic device, discrete gate or transistor logic, a discrete hardware component, or any combination thereof). In some cases, the processor **1535** may be configured to operate a memory array using a memory controller. In some other cases, a memory controller may be integrated into the processor **1535**. The processor **1535** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **1525**) to cause the device **1505** to perform various functions (e.g., functions or tasks supporting frequency resource selection for multiple channels). For example, the device **1505** or a component of the device **1505** may include a processor **1535** and memory **1525** coupled with the processor **1535**, the processor **1535** and memory **1525** configured to perform various functions described herein. The processor **1535** may be an example of a cloud-computing platform (e.g., one

or more physical nodes and supporting software such as operating systems, virtual machines, or container instances) that may host the functions (e.g., by executing code **1530**) to perform the functions of the device **1505**. The processor **1535** may be any one or more suitable processors capable of executing scripts or instructions of one or more software programs stored in the device **1505** (such as within the memory **1525**). In some implementations, the processor **1535** may be a component of a processing system. A processing system may generally refer to a system or series of machines or components that receives inputs and processes the inputs to produce a set of outputs (which may be passed to other systems or components of, for example, the device **1505**). For example, a processing system of the device **1505** may refer to a system including the various other components or subcomponents of the device **1505**, such as the processor **1535**, or the transceiver **1510**, or the communications manager **1520**, or other components or combinations of components of the device **1505**. The processing system of the device **1505** may interface with other components of the device **1505** and may process information received from other components (such as inputs or signals) or output information to other components. For example, a chip or modem of the device **1505** may include a processing system and an interface to output information, or to obtain information, or both. The interface may be implemented as or otherwise include a first interface configured to output information and a second interface configured to obtain information. In some implementations, the first interface may refer to an interface between the processing system of the chip or modem and a transmitter, such that the device **1505** may transmit information output from the chip or modem. In some implementations, the second interface may refer to an interface between the processing system of the chip or modem and a receiver, such that the device **1505** may obtain information or signal inputs, and the information may be passed to the processing system. A person having ordinary skill in the art will readily recognize that the first interface also may obtain information or signal inputs, and the second interface also may output information or signal outputs.

[0225] In some examples, a bus **1540** may support communications of (e.g., within) a protocol layer of a protocol stack. In some examples, a bus **1540** may support communications associated with a logical channel of a protocol stack (e.g., between protocol layers of a protocol stack), which may include communications performed within a component of the device **1505**, or between different components of the device **1505** that may be co-located or located in different locations (e.g., where the device **1505** may refer to a system in which one or more of the communications manager **1520**, the transceiver **1510**, the memory **1525**, the code **1530**, and the processor **1535** may be located in one of the different components or divided between different components).

[0226] In some examples, the communications manager **1520** may manage aspects of communications with a core network **130** (e.g., via one or more wired or wireless backhaul links). For example, the communications manager **1520** may manage the transfer of data communications for client devices, such as one or more UEs **115**. In some examples, the communications manager **1520** may manage communications with other network entities **105** and may include a controller or scheduler for controlling communications with UEs **115** in cooperation with other network entities **105**. In some examples, the communications manager **1520** may support an X2 interface within an LTE/LTE-A wireless communications network technology to provide communication between network entities **105**.

[0227] The communications manager **1520** may support wireless communication at a network entity in accordance with examples as disclosed herein. For example, the communications manager **1520** may be configured as or otherwise support a means for transmitting scheduling information that allocates a set of multiple uplink channels of a same channel type to a UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels. The communications manager **1520** may be configured as or otherwise support a means for transmitting an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels. The communications manager **1520** may be configured as or otherwise

support a means for receiving an uplink message via a first uplink channel based on identifying that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the first uplink channel includes a first set of frequency resources.

[0228] By including or configuring the communications manager **1520** in accordance with examples as described herein, the device **1505** may support techniques for improved communication reliability, reduced latency, improved user experience related to reduced processing, reduced power consumption, more efficient utilization of communication resources, improved coordination between devices, and longer battery.

[0229] In some examples, the communications manager **1520** may be configured to perform various operations (e.g., receiving, obtaining, monitoring, outputting, transmitting) using or otherwise in cooperation with the transceiver **1510**, the one or more antennas **1515** (e.g., where applicable), or any combination thereof. For example, the communications manager **1520** may be configured to receive or transmit messages or other signaling as described herein via the transceiver **1510**. Although the communications manager **1520** is illustrated as a separate component, in some examples, one or more functions described with reference to the communications manager **1520** may be supported by or performed by the processor **1535**, the memory **1525**, the code **1530**, the transceiver **1510**, or any combination thereof. For example, the code **1530** may include instructions executable by the processor **1535** to cause the device **1505** to perform various aspects of frequency resource selection for multiple channels as described herein, or the processor **1535** and the memory **1525** may be otherwise configured to perform or support such operations.

[0230] FIG. **16** shows a flowchart illustrating a method **1600** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The operations of the method **1600** may be implemented by a UE or its components as described herein. For example, the operations of the method **1600** may be performed by a UE **115** as described with reference to FIGS. **1** through **11**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

[0231] At **1605**, the method may include receiving scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels. The operations of **1605** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1605** may be performed by a scheduling information component **1025** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1605** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0232] At **1610**, the method may include selecting, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources. The operations of **1610** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1610** may be performed by an uplink channel selection component **1030** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1610** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0233] At **1615**, the method may include transmitting an uplink message via the first uplink channel based on the selecting. The operations of **1615** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1615** may be performed by an uplink message component **1035** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1615** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including

code **1135**), processor **1140** and/or bus **1145**.

[0234] At **1620**, the method may include refraining from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources. The operations of **1620** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1620** may be performed by an uplink message component **1035** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1620** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0235] FIG. **17** shows a flowchart illustrating a method **1700** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The operations of the method **1700** may be implemented by a UE or its components as described herein. For example, the operations of the method **1700** may be performed by a UE **115** as described with reference to FIGS. **1** through **11**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

[0236] At **1705**, the method may include receiving scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels. The operations of **1705** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1705** may be performed by a scheduling information component **1025** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1705** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0237] At **1710**, the method may include receiving an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels. The operations of **1710** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1710** may be performed by an uplink channel selection component **1030** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1710** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0238] At **1715**, the method may include selecting, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources. In some aspects, the UE selecting the first uplink channel may be based on the indication that uplink channel selection is enabled. The operations of **1715** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1715** may be performed by an uplink channel selection component **1030** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1715** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0239] At **1720**, the method may include transmitting an uplink message via the first uplink channel based on the selecting. The operations of **1720** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1720** may be performed by an uplink message component **1035** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1720** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0240] At **1725**, the method may include refraining from transmitting via at least a portion of a

second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources. The operations of **1725** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1725** may be performed by an uplink message component **1035** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1725** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0241] FIG. **18** shows a flowchart illustrating a method **1800** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The operations of the method **1800** may be implemented by a UE or its components as described herein. For example, the operations of the method **1800** may be performed by a UE **115** as described with reference to FIGS. **1** through **11**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally, or alternatively, the UE may perform aspects of the described functions using special-purpose hardware.

[0242] At **1805**, the method may include receiving scheduling information that allocates a set of multiple uplink channels of a same channel type to the UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels. The operations of **1805** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1805** may be performed by a scheduling information component **1025** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1805** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0243] At **1810**, the method may include selecting, from among the set of multiple uplink channels, a first uplink channel that includes a first set of frequency resources. The operations of **1810** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1810** may be performed by an uplink channel selection component **1030** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1810** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0244] At **1815**, the method may include transmitting an uplink message via the first uplink channel based on the selecting. The operations of **1815** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1815** may be performed by an uplink message component **1035** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1815** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0245] At **1820**, the method may include transmitting, within a subset of the first set of frequency resources that is common to the set of multiple uplink channels, UCI that indicates that the UE has selected the first uplink channel from among the set of multiple uplink channels. The operations of **1820** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1820** may be performed by a UCI component **1040** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1820** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0246] At **1825**, the method may include refraining from transmitting via at least a portion of a second uplink channel of the set of multiple uplink channels based on the selecting, the second uplink channel including a second set of frequency resources. The operations of **1825** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the

operations of **1825** may be performed by an uplink message component **1035** as described with reference to FIG. **10**. Additionally, or alternatively, means for performing **1825** may, but not necessarily, include, for example, antenna **1125**, transceiver **1115**, communications manager **1120**, memory **1130** (including code **1135**), processor **1140** and/or bus **1145**.

[0247] FIG. **19** shows a flowchart illustrating a method **1900** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The operations of the method **1900** may be implemented by a network entity or its components as described herein. For example, the operations of the method **1900** may be performed by a network entity as described with reference to FIGS. **1** through **7** and **12** through **15**. In some examples, a network entity may execute a set of instructions to control the functional elements of the network entity to perform the described functions. Additionally, or alternatively, the network entity may perform aspects of the described functions using special-purpose hardware.

[0248] At **1905**, the method may include transmitting scheduling information that allocates a set of multiple uplink channels of a same channel type to a UE, where the scheduling information indicates respective sets of frequency resources for the set of multiple uplink channels. The operations of **1905** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1905** may be performed by a scheduling information component **1425** as described with reference to FIG. **14**. Additionally, or alternatively, means for performing **1905** may, but not necessarily, include, for example, antenna **1515**, transceiver **1510**, communications manager **1520**, memory **1525** (including code **1530**), processor **1535** and/or bus **1540**.

[0249] At **1910**, the method may include transmitting an indication that uplink channel selection by the UE is enabled for the set of multiple uplink channels. The operations of **1910** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1910** may be performed by an uplink channel selection component **1430** as described with reference to FIG. **14**. Additionally, or alternatively, means for performing **1910** may, but not necessarily, include, for example, antenna **1515**, transceiver **1510**, communications manager **1520**, memory **1525** (including code **1530**), processor **1535** and/or bus **1540**.

[0250] At **1915**, the method may include receiving an uplink message via a first uplink channel based on identifying that the UE has selected the first uplink channel from among the set of multiple uplink channels, where the first uplink channel includes a first set of frequency resources. The operations of **1915** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **1915** may be performed by an uplink message component **1435** as described with reference to FIG. **14**. Additionally, or alternatively, means for performing **1915** may, but not necessarily, include, for example, antenna **1515**, transceiver **1510**, communications manager **1520**, memory **1525** (including code **1530**), processor **1535** and/or bus **1540**.

[0251] FIG. **20** shows a flowchart illustrating a method **2000** that supports frequency resource selection for multiple channels in accordance with one or more aspects of the present disclosure. The operations of the method **2000** may be implemented by a network entity or its components as described herein. For example, the operations of the method **2000** may be performed by a network entity as described with reference to FIGS. **1** through **7** and **12** through **15**. In some examples, a network entity may execute a set of instructions to control the functional elements of the network entity to perform the described functions. Additionally, or alternatively, the network entity may perform aspects of the described functions using special-purpose hardware.

[0252] At **2005**, the method may include transmitting scheduling information that allocates a plurality of uplink channels of a same channel type to a UE, wherein the scheduling information indicates respective sets of frequency resources for the plurality of uplink channels. The operations of **2005** may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of **2005** may be performed by a scheduling information component **1425**

as described with reference to FIG. 14. Additionally, or alternatively, means for performing 2005 may, but not necessarily, include, for example, antenna 1515, transceiver 1510, communications manager 1520, memory 1525 (including code 1530), processor 1535 and/or bus 1540.

[0253] At 2010, the method may include transmitting an indication of a subset of a first set of frequency resources that is common to the plurality of uplink channels, the first set of frequency resources included in the respective sets of frequency resources. The operations of 2010 may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of 2010 may be performed by a reserved resource component 1440 as described with reference to FIG. 14. Additionally, or alternatively, means for performing 2010 may, but not necessarily, include, for example, antenna 1515, transceiver 1510, communications manager 1520, memory 1525 (including code 1530), processor 1535 and/or bus 1540.

[0254] At 2015, the method may include transmitting an indication that uplink channel selection by the UE is enabled for the plurality of uplink channels. The operations of 2015 may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of 2015 may be performed by an uplink channel selection component 1430 as described with reference to FIG. 14. Additionally, or alternatively, means for performing 2015 may, but not necessarily, include, for example, antenna 1515, transceiver 1510, communications manager 1520, memory 1525 (including code 1530), processor 1535 and/or bus 1540.

[0255] At 2020, the method may include receiving, via the subset of the first set of frequency resources, an indication that the UE has selected, from among the plurality of uplink channels, at least a portion of the first set of frequency resources for transmitting the uplink message. The operations of 2020 may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of 2020 may be performed by an uplink channel selection component 1430 as described with reference to FIG. 14. Additionally, or alternatively, means for performing 2020 may, but not necessarily, include, for example, antenna 1515, transceiver 1510, communications manager 1520, memory 1525 (including code 1530), processor 1535 and/or bus 1540.

[0256] At 2025, the method may include identifying, based on receiving the indication, that the UE has selected a first uplink channel from among the plurality of uplink channels, wherein the first uplink channel comprises a first set of frequency resources. The operations of 2025 may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of 2025 may be performed by an uplink channel selection component 1430 as described with reference to FIG. 14. Additionally, or alternatively, means for performing 2025 may, but not necessarily, include, for example, antenna 1515, transceiver 1510, communications manager 1520, memory 1525 (including code 1530), processor 1535 and/or bus 1540.

[0257] At 2030, the method may include receiving an uplink message via the first uplink channel based at least in part on identifying that the UE has selected the first uplink channel from among the plurality of uplink channels. The operations of 2030 may be performed in accordance with examples as disclosed herein. In some examples, aspects of the operations of 2030 may be performed by an uplink channel selection component 1430 as described with reference to FIG. 14. Additionally, or alternatively, means for performing 2030 may, but not necessarily, include, for example, antenna 1515, transceiver 1510, communications manager 1520, memory 1525 (including code 1530), processor 1535 and/or bus 1540.

[0258] The following provides an overview of aspects of the present disclosure:

[0259] Aspect 1: A method for wireless communication at a UE, comprising: receiving scheduling information that allocates a plurality of uplink channels of a same channel type to the UE, wherein the scheduling information indicates respective sets of frequency resources for the plurality of uplink channels; selecting, from among the plurality of uplink channels, a first uplink channel that comprises a first set of frequency resources; transmitting an uplink message via the first uplink channel based at least in part on the selecting; and refraining from transmitting via at least a portion

of a second uplink channel of the plurality of uplink channels based at least in part on the selecting, the second uplink channel comprising a second set of frequency resources.

[0260] Aspect 2: The method of aspect 1, wherein receiving the scheduling information comprises: receiving, via the scheduling information, an indication that uplink channel selection by the UE is enabled for the plurality of uplink channels, wherein the UE selecting the first uplink channel is based at least in part on the indication that uplink channel selection is enabled.

[0261] Aspect 3: The method of aspect 2, wherein: the scheduling information comprises a DCI message; and the indication that uplink channel selection by the UE is enabled for the plurality of uplink channels comprises a format of the DCI message.

[0262] Aspect 4: The method of any of aspects 1 through 3, wherein the plurality of uplink channels are at least partially overlapping in a frequency domain, the method further comprising: transmitting, within a subset of the first set of frequency resources that is common to the plurality of uplink channels, UCI that indicates that the UE has selected the first uplink channel from among the plurality of uplink channels.

[0263] Aspect 5: The method of aspect 4, further comprising: selecting a second subset of the first set of frequency resources for transmitting the uplink message, wherein the uplink message is transmitted within the second subset of the first set of frequency resources, and wherein the UCI further indicates that the UE has selected the second subset for transmitting the uplink message.

[0264] Aspect 6: The method of any of aspects 4 through 5, further comprising: receiving, via the scheduling information or a control message that is different than the scheduling information, an indication of the subset of the first set of frequency resources that is common to the plurality of uplink channels.

[0265] Aspect 7: The method of any of aspects 1 through 3, wherein the plurality of uplink channels are at least partially overlapping in a frequency domain, the method further comprising: transmitting, via a subset of the first set of frequency resources, a DMRS sequence that indicates that the UE has selected the first uplink channel from among the plurality of uplink channels, wherein the subset of the first set of frequency resources is common to the plurality of uplink channels.

[0266] Aspect 8: The method of any of aspects 1 through 3, wherein each of the plurality of uplink channels comprises a respective set of reserved resources for UCI, the method further comprising: transmitting, via the respective set of reserved resources within the first uplink channel, UCI that indicates that the UE has selected the first uplink channel from among the plurality of uplink channels.

[0267] Aspect 9: The method of any of aspects 1 through 3, wherein each of the plurality of uplink channels is associated with a respective DMRS sequence, the method further comprising: transmitting, via a portion of the first uplink channel, the respective DMRS sequence for the first uplink channel to indicate that the UE has selected the first uplink channel from among the plurality of uplink channels.

[0268] Aspect 10: The method of any of aspects 1 through 9, wherein receiving the scheduling information comprises: receiving, within the scheduling information, a plurality of FDRA fields that each allocate a respective uplink channel of the plurality of uplink channels.

[0269] Aspect 11: The method of any of aspects 1 through 9, further comprising: receiving a control message that indicates a plurality of sets of frequency resources, wherein an FDRA field within the scheduling information indicates a subset of the plurality of sets of frequency resources, the subset comprising the respective sets of frequency resources for the plurality of uplink channels.

[0270] Aspect 12: The method of any of aspects 1 through 11, wherein receiving the scheduling information comprises: receiving a DCI message that allocates the plurality of uplink channels to the UE and indicates the respective sets of frequency resources for the plurality of uplink channels.

[0271] Aspect 13: The method of any of aspects 1 through 11, wherein receiving the scheduling

information comprises: receiving at least one configured grant that allocates the plurality of uplink channels to the UE and indicates the respective sets of frequency resources for the plurality of uplink channels.

[0272] Aspect 14: The method of any of aspects 1 through 13, wherein: the plurality of uplink channels allocated to the UE are overlapping in a time domain; and the plurality of uplink channels allocated to the UE are partially overlapping or non-overlapping in a frequency domain.

[0273] Aspect 15: A method for wireless communication at a network entity, comprising: transmitting scheduling information that allocates a plurality of uplink channels of a same channel type to a UE, wherein the scheduling information indicates respective sets of frequency resources for the plurality of uplink channels; transmitting an indication that uplink channel selection by the UE is enabled for the plurality of uplink channels; and receiving an uplink message via a first uplink channel based at least in part on identifying that the UE has selected the first uplink channel from among the plurality of uplink channels, wherein the first uplink channel comprises a first set of frequency resources.

[0274] Aspect 16: The method of aspect 15, wherein transmitting the scheduling information comprises: transmitting, within the scheduling information, the indication that uplink channel selection by the UE is enabled for the plurality of uplink channels.

[0275] Aspect 17: The method of any of aspects 15 through 16, wherein the plurality of uplink channels are at least partially overlapping in a frequency domain, the method further comprising: transmitting, via the scheduling information or a control message that is different than the scheduling information, an indication of a subset of the first set of frequency resources that is common to the plurality of uplink channels; and receiving, via the subset of the first set of frequency resources, an indication that the UE has selected, from among the plurality of uplink channels, at least a portion of the first set of frequency resources in the first uplink channel for transmitting the uplink message, wherein identifying that the UE has selected the first uplink channel is based on receiving the indication.

[0276] Aspect 18: The method of any of aspects 15 through 16, wherein each of the plurality of uplink channels comprises a respective set of reserved resources for UCI, the method further comprising: receiving, via the respective set of reserved resources within the first uplink channel, UCI that indicates that the UE selected the first uplink channel from among the plurality of uplink channels, wherein identifying that the UE has selected the first uplink channel is based on receiving the indication.

[0277] Aspect 19: The method of any of aspects 15 through 16, wherein each of the plurality of uplink channels is associated with a respective DMRS sequence, the method further comprising: receiving, via a portion of the first uplink channel, the respective DMRS sequence for the first uplink channel, wherein identifying that the UE selected the first uplink channel is based at least in part on receiving the respective DMRS sequence for the first uplink channel.

[0278] Aspect 20: The method of any of aspects 15 through 19, wherein transmitting the scheduling information comprises: transmitting, within the scheduling information, a plurality of FDRA fields that each allocate a respective uplink channel of the plurality of uplink channels.

[0279] Aspect 21: The method of any of aspects 15 through 19, further comprising: transmitting a control message that indicates a plurality of sets of frequency resources, wherein a FDRA field within the scheduling information indicates a subset of the plurality of sets of frequency resources, the subset comprising the respective sets of frequency resources for the plurality of uplink channels.

[0280] Aspect 22: The method of any of aspects 15 through 21, wherein transmitting the scheduling information comprises: transmitting a DCI message or at least one configured grant that allocates the plurality of uplink channels to the UE and indicates the respective sets of frequency resources for the plurality of uplink channels.

[0281] Aspect 23: The method of any of aspects 15 through 22, wherein no signaling is received

from the UE within at least a portion of a second uplink channel of the plurality of uplink channels, the second uplink channel comprising a second set of frequency resources set.

[0282] Aspect 24: The method of any of aspects 15 through 23, wherein: the plurality of uplink channels allocated to the UE are overlapping in a time domain; and the plurality of uplink channels allocated to the UE are partially overlapping or non-overlapping in a frequency domain.

[0283] Aspect 25: An apparatus for wireless communication, comprising a memory, transceiver, and at least one processor coupled with the memory and the transceiver, the at least one processor configured to perform a method of any of aspects 1 through 14.

[0284] Aspect 26: An apparatus for wireless communication at a UE, comprising at least one means for performing a method of any of aspects 1 through 14.

[0285] Aspect 27: A non-transitory computer-readable medium storing code for wireless communication at a UE, the code comprising instructions executable by a processor to perform a method of any of aspects 1 through 14.

[0286] Aspect 28: An apparatus for wireless communication, comprising a memory and at least one processor coupled with the memory, the at least one processor configured to perform a method of any of aspects 15 through 24.

[0287] Aspect 29: An apparatus for wireless communication at a network entity, comprising at least one means for performing a method of any of aspects 15 through 24.

[0288] Aspect 30: A non-transitory computer-readable medium storing code for wireless communication at a network entity, the code comprising instructions executable by a processor to perform a method of any of aspects 15 through 24.

[0289] It should be noted that the methods described herein describe possible implementations, and that the operations and the steps may be rearranged or otherwise modified and that other implementations are possible. Further, aspects from two or more of the methods may be combined.

[0290] Although aspects of an LTE, LTE-A, LTE-A Pro, or NR system may be described for purposes of example, and LTE, LTE-A, LTE-A Pro, or NR terminology may be used in much of the description, the techniques described herein are applicable beyond LTE, LTE-A, LTE-A Pro, or NR networks. For example, the described techniques may be applicable to various other wireless communications systems such as Ultra Mobile Broadband (UMB), Institute of Electrical and Electronics Engineers (IEEE) 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM, as well as other systems and radio technologies not explicitly mentioned herein.

[0291] Information and signals described herein may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

[0292] The various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed using a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor but, in the alternative, the processor may be any processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration).

[0293] The functions described herein may be implemented using hardware, software executed by a processor, firmware, or any combination thereof. If implemented using software executed by a processor, the functions may be stored as or transmitted using one or more instructions or code of a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described

herein may be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations.

[0294] Computer-readable media includes both non-transitory computer storage media and communication media including any medium that facilitates transfer of a computer program from one location to another. A non-transitory storage medium may be any available medium that may be accessed by a general-purpose or special-purpose computer. By way of example, and not limitation, non-transitory computer-readable media may include RAM, ROM, electrically erasable programmable ROM (EEPROM), flash memory, compact disk (CD) ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other non-transitory medium that may be used to carry or store desired program code means in the form of instructions or data structures and that may be accessed by a general-purpose or special-purpose computer, or a general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of computer-readable medium. Disk and disc, as used herein, include CD, laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc. Disks may reproduce data magnetically, and discs may reproduce data optically using lasers. Combinations of the above are also included within the scope of computer-readable media.

[0295] As used herein, including in the claims, “or” as used in a list of items (e.g., a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an example step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.”

[0296] The term “determine” or “determining” encompasses a variety of actions and, therefore, “determining” can include calculating, computing, processing, deriving, investigating, looking up (such as via looking up in a table, a database or another data structure), ascertaining and the like. Also, “determining” can include receiving (e.g., receiving information), accessing (e.g., accessing data stored in memory) and the like. Also, “determining” can include resolving, obtaining, selecting, choosing, establishing, and other such similar actions.

[0297] In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a dash and a second label that distinguishes among the similar components. If just the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label, or other subsequent reference label.

[0298] The description set forth herein, in connection with the appended drawings, describes example configurations and does not represent all the examples that may be implemented or that are within the scope of the claims. The term “example” used herein means “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other examples.” The detailed description includes specific details for the purpose of providing an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, known structures and devices are shown in block diagram form in order to avoid obscuring the concepts of the described examples.

[0299] The description herein is provided to enable a person having ordinary skill in the art to make or use the disclosure. Various modifications to the disclosure will be apparent to a person having ordinary skill in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not limited to the examples and designs described herein but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

Claims

1. A user equipment (UE), comprising: a transceiver; and a processing system that includes processor circuitry and memory circuitry that stores code, the processing system configured to: receive, via the transceiver, a dynamic grant that allocates a plurality of physical uplink shared channels to the UE, wherein the dynamic grant comprises one or more indications each indicating a respective set of frequency resources allocated for a respective physical uplink shared channel of the plurality of physical uplink shared channels; select, by the UE and from among the plurality of physical uplink shared channels, a first physical uplink shared channel that comprises a first set of frequency resources; transmit, via the transceiver, an uplink message via the first physical uplink shared channel based at least in part on the selecting; and refrain from transmitting, via the transceiver, via a first portion of a second physical uplink shared channel of the plurality of physical uplink shared channels based at least in part on the first portion of the second physical uplink shared channel overlapping with the first set of frequency resources of the first physical uplink shared channel in a frequency domain.
2. The UE of claim 1, wherein: each indication of the one or more indications indicates a respective pattern associated with the respective set of frequency resources in the frequency domain; or each indication of the one or more indications indicates a respective offset of the respective set of frequency resources in the frequency domain; or each indication of the one or more indications indicates a respective quantity of resource blocks allocated to the respective set of frequency resources in the frequency domain; or any combination thereof.
3. The UE of claim 1, wherein: the one or more indications comprise a plurality of frequency domain resource allocation fields.
4. The UE of claim 1, wherein, to receive the dynamic grant, the processing system is configured to: receive, via the transceiver and the dynamic grant, an indication that physical uplink shared channel selection by the UE is enabled for the plurality of physical uplink shared channels, wherein the processing system is configured to select the first physical uplink shared channel based at least in part on the indication that the physical uplink shared channel selection is enabled.
5. The UE of claim 1, wherein, to receive the dynamic grant, the processing system is configured to: receive, via the transceiver, a downlink control information message that comprises the dynamic grant, wherein a format of the downlink control information message indicates that physical uplink shared channel selection by the UE is enabled for the plurality of physical uplink shared channels.
6. The UE of claim 1, wherein the plurality of physical uplink shared channels are at least partially overlapping in the frequency domain, and the processing system is further configured to: transmit, via the transceiver and within a subset of the first set of frequency resources that is common to the plurality of physical uplink shared channels, uplink control information that indicates that the UE has selected the first physical uplink shared channel from among the plurality of physical uplink shared channels.
7. The UE of claim 6, wherein the processing system is further configured to: select a second subset of the first set of frequency resources for transmitting the uplink message, wherein the uplink message is transmitted within the second subset of the first set of frequency resources, and wherein the uplink control information further indicates that the UE has selected the second subset for transmitting the uplink message.

8. The UE of claim 6, wherein the processing system is further configured to: receive, via the transceiver and the dynamic grant or a control message that is different than the dynamic grant, an indication of the subset of the first set of frequency resources that is common to the plurality of physical uplink shared channels.

9. The UE of claim 1, wherein the plurality of physical uplink shared channels are at least partially overlapping in the frequency domain, and the processing system is further configured to: transmit, via the transceiver and a subset of the first set of frequency resources, a demodulation reference signal sequence that indicates that the UE has selected the first physical uplink shared channel from among the plurality of physical uplink shared channels, wherein the subset of the first set of frequency resources is common to the plurality of physical uplink shared channels.

10. The UE of claim 1, wherein each of the plurality of physical uplink shared channels comprises a respective set of reserved resources for uplink control information, and the processing system is further configured to: transmit, via transceiver and the respective set of reserved resources within the first physical uplink shared channel, first uplink control information that indicates that the UE has selected the first physical uplink shared channel from among the plurality of physical uplink shared channels.

11. The UE of claim 1, wherein each of the plurality of physical uplink shared channels is associated with a respective demodulation reference signal sequence, and the processing system is further configured to: transmit, via the transceiver and a portion of the first physical uplink shared channel, the respective demodulation reference signal sequence for the first physical uplink shared channel to indicate that the UE has selected the first physical uplink shared channel from among the plurality of physical uplink shared channels.

12. The UE of claim 1, wherein each indication of the one or more indications in the dynamic grant comprises one or more bits that allocate a respective physical uplink shared channel of the plurality of physical uplink shared channels.

13. The UE of claim 1, wherein the processing system is further configured to: receive, via the transceiver, a radio resource control message that indicates a plurality of sets of frequency resources, wherein the one or more indications within the dynamic grant indicate a subset of the plurality of sets of frequency resources, the subset comprising the respective sets of frequency resources for the plurality of physical uplink shared channels.

14. The UE of claim 1, wherein, to receive the dynamic grant, the processing system is configured to: receive, via the transceiver, a downlink control information message that allocates the plurality of physical uplink shared channels to the UE and comprises at least two frequency domain resource allocation fields for indicating the respective sets of frequency resources for the plurality of physical uplink shared channels, wherein the one or more indications comprise the at least two frequency domain resource allocation fields.

15. A network entity, comprising: a processing system that includes processor circuitry and memory circuitry that stores code, the processing system configured to: transmit a dynamic grant that allocates a plurality of physical uplink shared channels to a user equipment (UE), wherein the dynamic grant comprises a one or more indications each indicating a respective set of frequency resources allocated for a respective physical uplink shared channel of the plurality of physical uplink shared channels; transmit an indication that physical uplink shared channel selection by the UE is enabled for the plurality of physical uplink shared channels comprising the respective sets of frequency resources; and receive an uplink message via a first physical uplink shared channel based at least in part on identifying that the UE has selected the first physical uplink shared channel from among the plurality of physical uplink shared channels in accordance with the indication that the physical uplink shared channel selection by the UE is enabled, wherein the first physical uplink shared channel comprises a first set of frequency resources.

16. The network entity of claim 15, wherein: each indication of the one or more indications indicates a respective pattern associated with the respective set of frequency resources in a

frequency domain; or each indication of the one or more indications indicates a respective offset of the respective set of frequency resources in the frequency domain; or each indication of the one or more indications indicates a respective quantity of resource blocks allocated to the respective set of frequency resources in the frequency domain; or any combination thereof.

17. The network entity of claim 15, wherein the one or more indications comprise a plurality of frequency domain resource allocation fields.

18. The network entity of claim 15, wherein, to transmit the dynamic grant, the processing system is configured to: transmit a downlink control information message that comprises the dynamic grant, wherein the indication that physical uplink shared channel selection by the UE is enabled for the plurality of physical uplink shared channels comprises a format of the downlink control information message.

19. The network entity of claim 15, wherein the plurality of physical uplink shared channels are at least partially overlapping in a frequency domain, and the processing system is further configured to: receive, within a subset of the first set of frequency resources that is common to the plurality of physical uplink shared channels, uplink control information that indicates that the UE has selected the first physical uplink shared channel from among the plurality of physical uplink shared channels.

20. A method for wireless communication at a user equipment (UE), comprising: receiving a dynamic grant that allocates a plurality of physical uplink shared channels to the UE, wherein the dynamic grant comprises one or more indications each indicating a respective set of frequency resources allocated for a respective physical uplink shared channel of the plurality of physical uplink shared channels; selecting, by the UE and from among the plurality of physical uplink shared channels, a first physical uplink shared channel that comprises a first set of frequency resources; transmitting an uplink message via the first physical uplink shared channel based at least in part on the selecting; and refraining from transmitting via a first portion of a second physical uplink shared channel of the plurality of physical uplink shared channels based at least in part on the first portion of the second physical uplink shared channel overlapping with the first set of frequency resources of the first physical uplink shared channel in a frequency domain.
