

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250271684

Kind Code

A1

Publication Date

August 28, 2025

Inventor(s)

Inosaka; Yuji et al.

HEAD-UP DISPLAY DEVICE AND METHOD OF CONTROLLING HEAD-UP DISPLAY DEVICE

Abstract

A head-up display device including a backlight; a display; a polarization control element; an imaging optical system making first display light of a first polarization condition from an emission port via a first optical path having a first optical length to form a virtual image, and making second display light of a second polarization condition from the emission port via a second optical path having a second optical length longer than the first optical length to form a real image; and a controller controlling the polarization conditions of the display light and turning on and off of each light source. The controller performs control such that an area of the light sources turned-on more strongly than a predetermined intensity when the real image is displayed is made larger than an area of the light sources to be turned-on more strongly than a predetermined intensity when the virtual image is displayed.

Inventors: Inosaka; Yuji (Niigata, JP), Hoshi; Yukihisa (Niigata, JP), Sato; Yuri (Niigata, JP)

Applicant: Nippon Seiki Co., Ltd. (Niigata, JP)

Family ID: 1000008461907

Appl. No.: 19/037058

Filed: January 24, 2025

Foreign Application Priority Data

JP 2024-026158

Feb. 26, 2024

Publication Classification

Int. Cl.: G02B27/28 (20060101); G02B27/01 (20060101)

U.S. Cl.:

Background/Summary

TECHNICAL FIELD

[0001] The present disclosure relates to a head-up display device which emits display light from an emission port toward a projection member so as to allow virtual and real images of a display image represented by the display light to be visually recognized, and also relates to a method of controlling the head-up display device.

BACKGROUND ART

[0002] For example, Japanese Patent Application No. 2023-148856 (Patent Document 1 (PD1)), not yet been published at the time of filing the present application, describes a head-up display device that is provided with: an imaging optical system that includes a polarized reflective member with different transmittance (reflectance) depending on polarization conditions and a second reflective member for reflecting display light transmitted through the polarized reflective member, wherein the display light of a first polarization condition is emitted via a first optical path to be reflected on a surface of the polarized reflective member to form a virtual image and the display light of a second polarization condition is emitted via a second optical path to be transmitted through the polarized reflective member and reflected on the second reflective member to form a real image; and a single-system picture generation unit (PGU) disposed at a position inside a first focus of the imaging optical system in the first optical path and outside a second focus of the imaging optical system in the second optical path and switching between the first and second polarization conditions.

PRIOR ART DOCUMENT

Patent Document

[0003] Patent Document 1: Japanese Patent Application No. 2023-148856

SUMMARY OF INVENTION

Technical Problem

[0004] In the art described in PD1, for example, among the display lights (pixel lights) emitted from a single pixel of the PGU, pixel light emitted in a first direction is formed as the real image, and pixel light emitted in a second direction is formed as the virtual image.

[0005] In other words, when either one of the real image and the virtual image is displayed, the light emitted from the pixel in the direction for displaying the other image is useless and light utilization efficiency is thereby degraded.

[0006] FIGS. 15A and 15B depict irradiation directions (emission directions from a single pixel) of lights of light sources 214 at the time of displaying the virtual image and displaying the real image, respectively. In FIGS. 15A and 15B, symbol “L1” indicates a wide-ranging light ray area irradiated on a display 212 from light sources 214 mounted on a light-source circuit board 240 at the time of displaying the virtual image, and symbol “L2” indicates a wide-ranging light ray area irradiated on the display 212 from the light sources 214 mounted on the light-source circuit board 240 at the time of displaying the real image, in which the areas are surrounded by and illustrated with dash-dot lines. In a typical head-up display device, since it is sufficient that an image can be visually recognized at an eye box, the direction of light from a backlight (the direction of light emitted from a pixel) is restricted and thereby a backlight configuration bright and less wasteful at the eye box is realized. However, in a case where the virtual image and the real image are displayed, it is necessary to emit light in a wide range (e.g., directions A, B, C, and D) from a single pixel.

[0007] In a case where the real image is displayed, the wide-ranging light emitted from the single

pixel is divided into light in a range visually recognized as the real image at the eye box (e.g., in FIG. 15B, light irradiated on the display **212** in a direction indicated by a solid arrow) and light in a range not visually recognized as the real image (e.g., in FIG. 15B, lights C and D indicated by broken lines, in which the light C is irradiated perpendicularly on the display **212** and thus useless and the light D is irradiated outwardly on the display **212** and thus useless). On the other hand, in a case where the virtual image is displayed, the wide-ranging light emitted from the single pixel is divided into light in a range visually recognized as the virtual image at the eye box (e.g., in FIG. 15A, light irradiated on the display **212** in a direction indicated by a solid arrow) and light in a range not visually recognized as the virtual image (e.g., in FIG. 15A, lights A, C, and D indicated by broken lines, in which the light A is irradiated inwardly on the display **212** and thus useless, the light C is irradiated perpendicularly on the display **212** and thus useless, and the light D is irradiated outwardly on the display **212** and thus useless). It is known that an outer edge part of a light source region (light-source circuit board **240**), in which the light sources **214** are mounted, is likely to generate the light A that is visually recognized as the real image but not visually recognized as the virtual image.

[0008] In view of the above circumstances, the object of the present disclosure is to provide a head-up display device having a configuration for regulating the arrangement of light sources in a light source region, which are turned on when displaying the real image and when displaying the virtual image, and thereby suppressing a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and improving light utilization efficiency, and also to provide a method of controlling the head-up display device.

[0009] Other objects of the present disclosure will become apparent to those skilled in the art by referring to the following exemplary aspects and best mode of exemplary embodiments as well as the accompanying drawings.

Solution to Problem

[0010] Hereinafter, in order to easily understand the outline of the present disclosure, aspects according to the present disclosure will be exemplified.

[0011] A first aspect is a head-up display device provided with an emission port and emitting display light from the emission port toward a projection member so as to allow virtual and real images of a display image represented by the display light to be visually recognized, in which the head-up display device includes: a backlight that includes a plurality of light sources mounted thereon; a display that transmits illumination light emitted from the light sources and generates the display light; a polarization control element that switches between polarization conditions of the display light; an imaging optical system that causes first display light of a first polarization condition to be emitted from the emission port via a first optical path having a first optical path-length to form the virtual image, and causes second display light of a second polarization condition to be emitted from the emission port via a second optical path having a second optical path-length longer than the first optical path-length to form the real image; and a controller that controls the polarization conditions of the display light switched by the polarization control element and turning on and off of each of the light sources, wherein the controller performs control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image is to be displayed is larger than an area of the light sources to be turned-on more strongly than a predetermined intensity when the virtual image is displayed.

[0012] In this connection, the “predetermined intensity” refers to an emission intensity of light, set in a default state, that is emitted from the backlight provided with the light sources mounted thereon to the display when the virtual image or real image is to be displayed, and in this aspect, the level of the emission intensity is controlled based on the area of the light sources to be turned on. Thus, when the real image is to be displayed, the control is performed in such a manner that the area of the light sources to be turned-on more strongly than the predetermined intensity becomes

larger than the area of the light sources to be turned-on more strongly than the predetermined intensity for displaying the virtual image. In addition, the “area of the light sources to be turned-on” refers, as depicted in FIG. 8 for example, to a mount area of the light sources **14** to be turned-on (a turn-on area “A” upon generating virtual image, a turn-on area “B” upon generating real image) defined on the light-source circuit board **140** of the backlight **11**, among the plurality of light sources **14** mounted on the light-source circuit board **140**. In the first aspect, the controller performs the control such that, when the real image is to be displayed, the area of the light sources to be turned-on more strongly than a predetermined intensity is made larger than the area of the light sources to be turned-on more strongly than a predetermined intensity when the virtual image is displayed, and thus, for example, performing control such that, when the real image is displayed, the outer periphery of the light source region is turned on, whereas when the virtual image is displayed, the outer periphery of the light source region, which is not visually recognized as the virtual image, is turned off, makes it possible to eliminate a difference in brightness between the time of displaying the real image RI and the time of displaying the virtual image VI while suppressing the generation of useless light, and thus to improve light utilization efficiency. In this way, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

[0013] In a second aspect depending on the first aspect, the controller may further perform control such that, when the display image is changed so as to switch from the virtual image to the real image, a light source disposed at a mount region not overlapping with the display when viewing a light-source circuit board of the backlight from a normal direction, on which the light sources are mounted, is turned-on more strongly than the predetermined intensity.

[0014] In the second aspect, when the display image is changed so as to switch the virtual image to the real image, the controller performs control such that, as depicted in FIG. 7B for example, light sources **14** (light beams indicated by solid arrows in the drawing) disposed at a mount region (i.e., outer peripheries Y1, Y2 of a light-source circuit board **140**) not overlapping with a display **12** when viewing the light-source circuit board **140** of a backlight **11** from a normal direction, on which the light sources **14** are mounted, are turned-on more strongly than the predetermined intensity, and thereby makes it possible to suppress a disadvantage such that, when either one of the real image and the virtual image (e.g., real image) is displayed, light emitted from a pixel in a direction for displaying the other image (e.g., virtual image) is useless, and to improve light utilization efficiency. Note that, in FIGS. 7A and 7B, a solid arrow indicates a light beam used for display, and a broken arrow indicates a light beam not used for display.

[0015] In a third aspect depending on the first aspect, the controller may perform control such that the area of the light sources mounted on a light-source circuit board of the backlight, which are to be turned-on more strongly than the predetermined intensity when the real image is to be displayed, is larger than the area of the light sources mounted on the light-source circuit board, which are turned-on more strongly than the predetermined intensity when the virtual image is displayed, along a long-side direction of a rectangular region of the display.

[0016] In the third aspect, the controller performs control such that, as depicted in FIG. 8 for example, the area of the light sources **14** mounted on the light-source circuit board **140** of the backlight (turn-on area “B” upon generating real image), which are to be turned-on more strongly than a predetermined intensity when the real image is to be displayed, is made larger than the area of the light sources mounted on the light-source circuit board **140** (turn-on area “A” upon generating virtual image), which are turned-on more strongly than a predetermined intensity when the virtual image is displayed, along the long-side direction “H” of the display **12**. Alternatively, in the case of switching from a real image display to a virtual image display, control may be adopted such that, as depicted in FIG. 9 for example, the light sources **14** on outer peripheries in a short-side direction “V” (upper and lower rows) of the turn-on area “B” upon generating real image are

turned off.

[0017] In a fourth aspect depending on the first aspect, the controller may perform control such that the area of the light sources mounted on a light-source circuit board of the backlight, which are to be turned-on more strongly than the predetermined intensity when the real image is to be displayed, is larger than the area of the light sources mounted on the light-source circuit board, which are turned-on more strongly than the predetermined intensity when the virtual image is displayed, along each of long-side and short-side directions of a rectangular region of the display.

[0018] In the fourth aspect, the controller performs control such that, as depicted in FIGS. 10A and 10B for example, the area of the light sources 14 mounted on the light-source circuit board 140 of the backlight 11 (turn-on area “B” upon generating real image), which are to be turned-on more strongly than the predetermined intensity when the real image is to be displayed, is made larger than the area of the light sources 14 mounted on the light-source circuit board 140 (turn-on area “A” upon generating virtual image), which are turned-on more strongly than the predetermined intensity when the virtual image is displayed, along each of the long-side direction “H” and short-side direction “V” of the display. Therefore, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and to improve light utilization efficiency. Not limited to the turning-on patterns of the light sources 14 depicted in FIGS. 10A and 10B, other control may be adopted such that: (1) all light sources 14 arranged on outer peripheries of the light-source circuit board 140 are turned off; (2) the light sources 14 arranged at one periphery are turned off; (3) one periphery of each of the long “H” and short “V” sides is turned off; (4) a part of the light sources 14 is turned off when displaying the real image and then the part of the light sources 14 turned-off for displaying the real image is turned on when displaying the virtual image, and so forth.

[0019] In a fifth aspect depending on the first aspect, the controller may perform control such that the area of the light sources mounted on a light-source circuit board of the backlight, which are to be turned-on more strongly than the predetermined intensity when the real image is to be displayed, is larger than the area of the light sources mounted on the light-source circuit board, which are turned-on more strongly than the predetermined intensity when the virtual image is displayed, along each of long-side and short-side directions of a rectangular region of the display, and that an increment of the area of the light sources made larger along the long-side direction is larger than an increment of the area of the light sources made larger along the short-side direction.

[0020] In the fifth aspect, the controller performs the control such that, as depicted in FIGS. 10A and 10B for example, when the real image is to be displayed, the area of the light sources 14 mounted on the light-source circuit board 140 of the backlight 11 (turn-on area “B” upon generating real image), which are to be turned-on more strongly than the predetermined intensity, is made larger than the area of the light sources 14 mounted on the light-source circuit board 140 (turn-on area “A” upon generating virtual image), which are turned-on more strongly than the predetermined intensity when the virtual image is displayed, along each of the long-side direction “H” and short-side direction “V” of the display 12, and that an increment of the area of the light sources made larger along the long-side direction H is larger than an increment of the area of the light sources made larger along the short-side direction V, and thereby makes it possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and to more effectively improve light utilization efficiency.

[0021] A sixth aspect is a head-up display device provided with an emission port and emitting display light from the emission port toward a projection member so as to allow virtual and real images of a display image represented by the display light to be visually recognized, in which the head-up display device includes: a first backlight that includes a plurality of first light sources mounted thereon; a first display that transmits illumination light from the first light sources and

generates first display light; a second backlight that includes a plurality of second light sources mounted thereon; a second display that transmits illumination light from the second light sources and generates second display light; an imaging optical system that causes the first display light to be emitted from the emission port via a first optical path having a first optical path-length to form the virtual image, and causes the second display light to be emitted from the emission port via a second optical path having a second optical path-length longer than the first optical path-length to form the real image; a first controller that controls turning on and off of each of the first light sources; and a second controller that controls turning on and off of each of the second light sources, wherein the first controller performs control such that the first light sources are turned-on more strongly than a predetermined intensity when the virtual image is to be displayed by the first display light, and wherein the second controller performs control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image is to be displayed by the second display light is larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image is displayed.

[0022] In the sixth aspect, the head-up display device that includes dual systems for generating virtual images and real images, each including the light sources of the backlight, the display and the controller, and shares the imaging optical system, has a configuration in which the first controller performs the control such that the first light sources are turned-on more strongly than a predetermined intensity when the virtual image is to be displayed by the first display light, and the second controller performs the control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image is to be displayed by the second display light is made larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image is displayed. Due to the above configuration, for example, performing control such that, when the real image is displayed, the outer periphery of a light source region is turned on, whereas when the virtual image is displayed, the outer periphery of the light source region, which is not visually recognized as the virtual image, is turned off, makes it possible to eliminate a difference in brightness between the time of displaying the real image and the time of displaying the virtual image while suppressing the generation of useless light, and thus to improve light utilization efficiency. In this way, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

[0023] A seventh aspect is a method of controlling a head-up display device including a backlight that includes a light-source circuit board provided with a plurality of light sources mounted thereon; a display that transmits illumination light from the light sources of the backlight and generates display light; a polarization control element that switches between polarization conditions of the display light; an imaging optical system that causes first display light of a first polarization condition to be emitted from an emission port via a first optical path having a first optical path-length to form a virtual image, and causes second display light of a second polarization condition to be emitted from the emission port via a second optical path having a second optical path-length longer than the first optical path-length to form a real image; and a controller that controls the polarization conditions of the display light switched by the polarization control element and turning on and off of each of the light sources of the backlight, in which the method includes: switching, by the controller, the imaging optical system from the first optical path to the second optical path to change a display image from the virtual image to the real image; and performing, by the controller, control such that an area of a light source region of the light sources mounted on the light-source circuit board, which are to be turned-on more strongly than a predetermined intensity when the real image is to be displayed, is larger than an area of a light source region of the light sources to be turned-on more strongly than a predetermined intensity when the virtual image is displayed.

[0024] In the seventh aspect, the controller executes a procedure (step) of performing the control such that, when the real image is to be displayed, the area of the light sources to be turned-on more strongly than the predetermined intensity is made larger than the area of the light sources to be turned-on more strongly than the predetermined intensity when displaying the virtual image. When executing the above procedure, the controller performs the control such that, for example, the outer periphery of the light source region is turned on when displaying the real image, and on the other hand, the outer periphery of the light source region, which is not visually recognized as the virtual image, is turned off when displaying the virtual image, so that it is possible to eliminate a difference in brightness between the time of displaying the real image and the time of displaying the virtual image while suppressing the generation of useless light, and thus to improve light utilization efficiency. In this way, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

[0025] An eighth aspect is a method of controlling a head-up display device provided with an emission port and emitting display light from the emission port toward a projection member so as to allow virtual and real images of a display image represented by the display light to be visually recognized, the head-up display device including a first backlight that includes a plurality of first light sources mounted thereon; a first display that transmits illumination light from the first light sources and generates first display light; a second backlight that includes a plurality of second light sources mounted thereon; a second display that transmits illumination light from the second light sources and generates second display light; an imaging optical system that causes the first display light to be emitted from the emission port via a first optical path having a first optical path-length to form the virtual image, and causes the second display light to be emitted from the emission port via a second optical path having a second optical path-length longer than the first optical path-length to form the real image; a first controller that controls turning on and off of each of the first light sources; and a second controller that controls turning on and off of each of the second light sources, in which the method includes: performing, by the first controller, control such that the first light sources are turned-on more strongly than a predetermined intensity when the virtual image is to be displayed by the first display light; and performing, by the second controller, control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image is to be displayed by the second display light is larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image is displayed.

[0026] In the eighth aspect, the head-up display device that is provided with dual systems for generating the virtual images and the real images, each including the light sources of the backlight, the display and the controller, and shares the imaging optical system, has a configuration for executing procedures (steps) in which the first controller performs the control such that the first light sources are turned-on more strongly than a predetermined intensity when the virtual image is to be displayed by the first display light, and the second controller performs the control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image is to be displayed by the second display light is made larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image is displayed. When executing the above procedure, the controller performs the control such that, for example, the outer periphery of the light source region is turned on when displaying the real image, and on the other hand, the outer periphery of the light source region, which is not visually recognized as the virtual image, is turned off when displaying the virtual image, so that it is possible to eliminate a difference in brightness between the time of displaying the real image and the time of displaying the virtual image while suppressing the generation of useless light, and thus to improve light utilization efficiency. In this way, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

[0027] Those skilled in the art will readily appreciate that the exemplary aspects according to the present disclosure may be further modified without departing from the spirit of the present disclosure.

Description

BRIEF DESCRIPTION OF DRAWINGS

[0028] FIG. 1 is a diagram depicting an exemplary configuration of a head-up display device according to a first embodiment of the present disclosure, which includes an imaging optical system at the time of displaying a virtual image.

[0029] FIG. 2 is a diagram depicting an exemplary configuration of the head-up display device according to the first embodiment of the present disclosure, which includes an imaging optical system at the time of displaying a real image.

[0030] FIGS. 3A and 3B are diagrams depicting an exemplary lens configuration and optical path, between a backlight and a display, in the head-up display device according to the first embodiment of the present disclosure when the virtual image is displayed.

[0031] FIGS. 4A and 4B are diagrams depicting an exemplary lens configuration and optical path, between a backlight and a display, in the head-up display device according to the first embodiment of the present disclosure when the real image is displayed.

[0032] FIG. 5 is a diagram depicting an exemplary configuration of a control system of the head-up display device according to the first embodiment of the present disclosure.

[0033] FIG. 6 is a flowchart depicting an exemplary operation of the control system of the head-up display device according to the first embodiment of the present disclosure.

[0034] FIGS. 7A and 7B are diagrams depicting irradiation directions of light beams from each of a plurality of light sources mounted on a light-source circuit board of the backlight when viewing the light sources from a normal direction, at the time of displaying the virtual image and the real image, respectively, in the head-up display device according to the first embodiment of the present disclosure.

[0035] FIG. 8 is a diagram depicting an example of a first light-source turning-on pattern of the light sources mounted on the backlight, at the time of displaying the virtual image and the real image in the head-up display device according to the first embodiment of the present disclosure.

[0036] FIG. 9 is a diagram depicting an example of a second light-source turning-on pattern of the light sources mounted on the backlight, at the time of displaying the virtual image and the real image in the head-up display device according to the first embodiment of the present disclosure.

[0037] FIGS. 10A and 10B are diagrams depicting an example of a third light-source turning-on pattern of the light sources mounted on the backlight, at the time of displaying the virtual image and the real image in the head-up display device according to the first embodiment of the present disclosure.

[0038] FIG. 11 is a diagram depicting an example of a fourth light-source turning-on pattern of the light sources mounted on the backlight, at the time of displaying the virtual image and the real image in the head-up display device according to the first embodiment of the present disclosure.

[0039] FIG. 12 is a diagram depicting an exemplary configuration of a head-up display device according to a second embodiment of the present disclosure, which includes an imaging optical system at the time of displaying a virtual image.

[0040] FIG. 13 is a diagram depicting an exemplary configuration of a control system of the head-up display device according to the second embodiment of the present disclosure.

[0041] FIG. 14 is a flowchart depicting an exemplary operation of the control system of the head-up display device according to the second embodiment of the present disclosure.

[0042] FIGS. 15A and 15B are reference diagrams explaining the irradiation directions of light

from light sources, in which FIG. 15A depicts the case of displaying a virtual image and FIG. 15B depicts the case of displaying a real image.

DESCRIPTION OF EMBODIMENTS

[0043] The best mode of exemplary embodiments described below is used for easy understanding of the present disclosure. Therefore, it should be noted by those skilled in the art that the present disclosure is not unduly limited by the embodiments described below.

Configuration of First Embodiment

[0044] Hereinafter, a first embodiment of the present disclosure will be described with reference to the drawings. FIG. 1 is a diagram depicting a configuration in a case of generating a virtual image in a head-up display device (hereinafter, simply referred to as a HUD device 1A) according to the first embodiment, and FIG. 2 is a diagram depicting a configuration in a case of generating a real image.

[0045] In FIGS. 1 and 2, the HUD device 1A includes, for example, a backlight 11 that includes light sources mounted thereon and emitting white light (see, e.g., “14” in FIGS. 7A and 7B), the light sources being light emitting diodes mounted on a light-source circuit board (see, e.g., “140” in FIGS. 7A and 7B) and emitting light in a visible wavelength range; a display 12 that generates an image based on incident light from the backlight 11 (light sources 14) and displays the image while switching the polarization of emission light between first polarization (a first polarization condition) and second polarization (a second polarization condition) different from each other; an imaging optical system 13 that includes a plurality of mirrors (reflective members) for reflecting display light “L” representing the image displayed on the display 12 (in FIG. 1, first display light L1 representing the display image of the virtual image VI, and in FIG. 2, second display light L2 representing the display image of the real image RI) toward a windshield WS as a projection member; and a controller 15 that performs control of the display contents of the display 12, switching control between the first and second polarizations, and control of turning on and off of the light sources 14 of the backlight 11. The backlight 11, the display 12, the imaging optical system 13, and the controller 15 are housed in a housing 16. The housing 16 is provided with an emission port 17 (opening) from which the display light L is emitted, and a cover glass 18 is disposed in the emission port 17 for protecting the interior of the housing.

[0046] The imaging optical system 13 causes the first display light L1 of the first polarization condition (first polarization) to be emitted from the emission port 17 via a first optical path OP1 having a first optical path-length to form the virtual image VI (FIG. 1), and causes the second display light L2 of the second polarization condition (second polarization) to be emitted from the emission port 17 via a second optical path having a second optical path-length longer than the first optical path-length to form the real image RI (FIG. 2). Thus, the imaging optical system 13 includes a first mirror 131, a second mirror 132, and a third mirror 133, each having a concave shape. The first mirror 131 reflects the first display light L1 as the first polarization, and transmits the second display light L2 as the second polarization. The second mirror 132 reflects the second display light L2 transmitted through the first mirror 131. The respective display lights (first display light L1 and second display light L2) reflected by the first mirror 131 and the second mirror 132 are guided to the third mirror 133, reflected by the third mirror 133, and emitted toward the windshield WS, so as to allow an occupant DR to visually recognize the respective display images.

[0047] Thus, the first optical path OP1 passes through the backlight 11 (light sources 14), the display 12, the first mirror 131, the third mirror 133, the emission port 17, and the windshield WS, while the second optical path OP2 passes through the backlight 11 (light sources 14), the display 12, the first mirror 131, the second mirror 132, the third mirror 133, the emission port 17, and the windshield WS, so as to ensure the visual recognition by the occupant DR. Therefore, the optical path-length of the second optical path OP2 is longer by the second mirror 132. Note that an infinite number of light beams are actually emitted from the display 12, but in FIGS. 1 and 2, a light beam emitted from the center of the display 12 and passing through the center of an eye box is depicted

as a representative light beam by a symbol “L”, in order to simplify the description. In FIGS. 1, 2, 7A and 7B, the representative light beam emitted from the center of the display **12** is depicted by a solid line, a light beam emitted from a top end of the display **12** is depicted by a dash-dot line, and a light beam emitted from a bottom end of the display **12** is depicted by a dash-dot-dot line.

[0048] The HUD device **1A** according to the first embodiment of the present disclosure is disposed below the windshield **WS** (e.g., inside an instrument panel) of the vehicle **C**, emits the display light **L** (first display light **L1** and second display light **L2**), and projects the display light **L** on the windshield **WS**. The display light **L** is generated by the backlight **11** (light sources **14**) and the display **12**, both provided within the HUD device **1A**. The display light **L** emitted from the display **12** travels along the imaging optical system **13** and is emitted from the emission port **17** of the housing **16** through the cover glass **18**. The occupant **DR** in the vehicle **C** views the display light **L** reflected by the windshield **WS**, and thus is able to visually recognize the virtual image **VI** as depicted in FIG. 1 on the far side of the windshield **WS** and the real image **RI** as depicted in FIG. 2 on the near side of the windshield **WS**.

[0049] In the virtual image **VI** depicted in FIG. 1, information highly necessary to call attention to the occupant **DR** is displayed on the far side of the windshield **WS** as seen from the occupant **DR**, which includes, for example, vehicle information such as the speed or engine revs of the vehicle **C**, routing assistance such as turn-by-turn or a map, a blind spot indicator, a warning such as a speed limit excess warning, etc. As examples of the real image **RI** depicted in FIG. 2, entertainment contents, an assistant or agent supporting the occupant **DR**, a character indicating the assistant or agent, etc., are displayed on the near side of the windshield **WS** as seen from the occupant **DR**. Such display properties provide a driving environment with reduced need for viewpoint movement and eye focal-length adjustment. The virtual image **VI** and the real image **RI** also include a background part in addition to characters and icons indicating the above-described information, the background part having, e.g., a substantially rectangular shape in a plan view as seen from the occupant **DR**.

[0050] The display **12** includes, for example, a display element **121** of a thin film transistor (TFT) type (see FIG. 5), and a polarization control element **122** that is provided closer to the emission port **17** along the optical path than the display element **121** and switches the polarization of the emitted display light **L** between the first polarization and the second polarization different from each other. For example, the first polarization may be S-polarization and the second polarization may be P-polarization, or vice versa. Further, not limited to S or P-polarization, it is sufficient that the polarization angles of the first and second polarizations are different from each other, and it is preferable that, for example, the polarization angles are different from each other by at least 22.5 degrees.

[0051] As depicted in FIGS. 1 and 2, it is desirable that the display **12** is disposed to be inclined with respect to the axial direction (optical axis) of the light beam of the display light **L**, in order to exclude stray light (light leaking from the light sources **14** of the backlight **11**) and external light (light entering from the outside) from the optical path of the display light **L**.

[0052] The display element **121** is connected to a display controller **151** as depicted in FIG. 5 described later, and forms light representing a graphic of an arbitrary shape in accordance with a signal sent from the display controller **151**. The polarization control element **122** extracts only light beams with specific polarizations, more specifically, light beams with the above-described first or second polarizations, among light beams emitted from the display element **121**, and performs control of switching the light beams. The polarization control element **122** is connected to a display driver **152** as depicted in FIG. 5 described later, and switches polarizations in accordance with a signal sent from the display driver **152**.

[0053] The switching of polarizations by the polarization control element **122** may be performed by electrical processing, or may be performed by using a polarizing plate (see “**117**” in FIGS. 3A and 3B described later) or a wave plate, that is disposed closer to the emission port **17** than the

polarization control element **122**, and physically rotating the plate at a predetermined angle with respect to a central axis defined along the direction of optical axis. In any case, the switching of polarizations is performed under the control of the display driver **152**.

[0054] In this connection, such a configuration is considered that, for example, the first polarization is S-polarization (S-polarization with respect to the first mirror **131**), the second polarization is P-polarization (P-polarization with respect to the first mirror **131**), the first mirror **131** is a mirror that reflects a light beam of the said S-polarization to the first mirror **131** and transmits a light beam of the said P-polarization, and the second mirror **132** is a mirror that reflects a light beam of the said P-polarization to the first mirror **131** and transmits a light beam of the said S-polarization. In the above configuration, the first display light **L1** with the S-polarization is reflected by the first mirror **131** and is guided to the third mirror **133**. Also, the second display light **L2** with the P-polarization is transmitted through the first mirror **131**, is reflected by the second mirror **132**, and is guided to the third mirror **133**. By setting the configuration of the imaging optical system **13** and the polarizations of the display lights (the first display light **L1** and the second display light **L2**) as described above, it is possible to generate display images different from each other by the display lights **L1** and **L2**.

[0055] In FIG. **2**, since the optical focus **F** is located closer to the emission port **17** than the first mirror **131**, it is possible to display the real image **RI** at any appropriate positions in front of the occupant **DR**. In this connection, if the optical focus **F** is located closer to the display **12** than the first mirror **131**, the optical focus **F** is being spaced from the second mirror **132**, and the real image **RI** becomes displayed at a position gradually closer to the occupant **DR** in a larger size in accordance with spacing degrees, which makes the real image **RI** very difficult to view for the occupant **DR**. Thus, it is preferable that the optical focus **F** is near the second mirror **132**, and in the HUD device **1A** according to the first embodiment, the imaging optical system **13** is arranged in such a manner that the optical focus **F** is positioned at least between the first mirror **131** and the second mirror **132**.

[0056] The controller **15** controls the polarization conditions of the display light **L** switched by the polarization control element **122** and the turning-on and off of each of the light sources **14**. The controller **15** performs control such that an area of the light sources **14** to be turned-on more strongly than a predetermined intensity when the real image **RI** is to be displayed is made larger than an area of the light sources **14** turned-on more strongly than a predetermined intensity when the virtual image **VI** is displayed. The configuration and operation of the controller **15** will be described later with reference to FIGS. **5** and **6**.

[0057] Reference is now made to FIGS. **3A** and **3B**. FIG. **3A** depicts a lens configuration and optical path as viewed in H-direction, and FIG. **3B** depicts a lens configuration and optical path as viewed in V-direction, at the time of displaying the virtual image **VI**. In FIGS. **3A** and **3B**, light emitted from LEDs **111** provided as the backlight **11** (light sources **14**) comes into parallel light substantially parallel to an optical axis by a condenser lens **113**, in both the H and V-directions. The light receiving surface of a first lenticular lens **114**, on a side facing the LEDs **111**, is structured in such a manner that a plurality of cylindrical lenses, each having a convex curved surface facing the LEDs **111** as viewed in a V-direction cross-section, are disposed side-by-side along the V-direction. The light emitting surface of the first lenticular lens **114** is structured in such a manner that a plurality of cylindrical lenses, each having a convex curved surface on a side emitting the second display light **L2** as viewed in a V-direction cross-section, are disposed side-by-side along the V-direction. Due to the above structure, the first lenticular lens **114** condenses the light of the LEDs **111** in relation to the V-direction to form a multiple image.

[0058] The light receiving surface of a second lenticular lens **115**, on a side facing the LEDs **111**, is structured in such a manner that a plurality of cylindrical lenses, each having a convex curved surface facing the LEDs **111** as viewed in an H-direction cross-section, are disposed side-by-side along the H-direction. The light emitting surface of the second lenticular lens **115** is structured as a

toroidal surface having a concave shape in both the V and H-directions. Due to the above structure, the second lenticular lens **115** condenses the light of the LEDs **111** in relation to the H-direction to form a multiple image, and aligns the direction of light with respect to the subsequent imaging optical system **13** (see FIGS. **1** and **2**). The second lenticular lens **115** for displaying the virtual image VI is referred to as a first lens **115a**.

[0059] The second display light L2 emitted from the first lens **115a** is diffused by a diffuser plate **117** (not depicted in FIG. **1**) to reduce uneven brightness, etc. The second display light L2 diffused by the diffuser plate **117** enters a liquid crystal panel (LCP) **116** provided as the display **12**, generates an image in accordance with the control of a control board (the controller **15** in FIG. **1**), and is emitted to the first mirror **131** of the subsequent imaging optical system **13**. Due to the above lens configuration and optical path, the occupant DR is able to visually recognize the virtual image VI with appropriate luminance and uniformity.

[0060] FIGS. **4A** and **4B** are diagrams depicting an example of a lens configuration and optical path (second optical path OP2) in the HUD device **1A** of the present embodiment when the real image RI is displayed. FIG. **4A** depicts a lens configuration and optical path as viewed in H-direction, and FIG. **4B** depicts a lens configuration and optical path as viewed in V-direction. In FIGS. **4A** and **4B**, the condenser lens **113** and the first lenticular lens **114** have the same structures as those in FIGS. **3A** and **3B**. Thus, the condenser lens **113** turns the light emitted from the LEDs **111** into parallel light in both the H and V-directions, and the first lenticular lens **114** condenses the light of the LEDs **111** in relation to the V-direction to form a multiple image.

[0061] The second lenticular lens **115** also condenses the light of the LEDs **111** in relation to the H-direction to form a multiple image, in the same manner as described in FIG. **3A**. Thus, analogous to FIG. **3A**, the light receiving surface of the second lenticular lens **115**, on a side facing the LEDs **111**, is structured in such a manner that a plurality of cylindrical lenses, each having a convex curved surface facing the LEDs **111** as viewed in an H-direction cross-section, are disposed side-by-side along the H-direction. On the other hand, the light emitting surface is structured as a toroidal surface having a convex shape in both the V and H-directions, in order to realize light distribution characteristics such that the light sources **14** (LEDs **111**) for displaying the real image RI emit illumination light so as to converge on the display **12** for displaying the real image RI while the light sources **14** for displaying the virtual image VI emit illumination light so as to diverge on the display **12**. The light emitting surface having the convex shape makes the light distribution characteristics narrower in both the H and V-directions. The second lenticular lens **115** for displaying the real image RI is referred to as a second lens **115b**.

[0062] The first display light L1 emitted from the second lens **115b** is diffused by the diffuser plate **117** (not depicted in FIG. **1**) to reduce uneven brightness, etc., enters the display **12** (LCP **116**), generates an image (first display light L1) in accordance with the control of the control board (controller **15**), and is emitted to the first mirror **131** of the subsequent imaging optical system **13**. As depicted in FIGS. **4A** and **4B**, when the real image RI is displayed, the optical axes in both the H and V-directions are made to intersect between the windshield WS and the viewpoint EB (eye box) of the occupant DR as a viewer, in order to generate the real image RI. The intersections of the optical axes may be arbitrarily set according to the position and magnification of the real image RI to be displayed. Due to the above lens configuration and optical path, the occupant DR is able to visually recognize the real image RI with appropriate luminance and uniformity.

[0063] FIG. **5** is a functional block diagram depicting a configuration of a picture generation unit (PGU) in the HUD device **1A** according to the first embodiment of the present disclosure. Note that FIG. **5** illustrates only a minimum necessary configuration directly related to the present disclosure, and other known configurations are omitted. In FIG. **5**, the PGU **10** includes the controller **15**, the backlight **11** (light sources **14**), and the display **12**, also depicted in FIGS. **1** and **2**. The controller **15** includes a display controller **151** that issues a command to the display **12** so as to generate light representing a graphic of an arbitrary shape, on the basis of, for example, information sent from

various devices **30**, such as a vehicle speed sensor, a navigation unit, RADAR (Radio Detecting and Ranging), LiDAR (Laser Imaging Detection and Ranging), etc.; and a display driver **152** that generates image by using the light emitted from the light sources **14** of the backlight **11** on the basis of, for example, a signal sent from a switch **20** for changing a driving mode of the vehicle **C** (manual driving, automatic driving), switches the polarization of the emission light between the first and second polarization condition different from each other, and thus performs switching control of polarization direction of the display **12** that generates the display light (first display light **L1** and second display light **L2**) representing the display image.

[0064] The controller **15** also includes a light source driver **153** that controls supply power necessary for turning on and off the light sources **14** mounted on the light-source circuit board **140** (see FIG. 7A) included in the backlight **11**. The light source driver **153** controls the ON/OFF timing of each LED **111** (see FIGS. 3A, 3B, 4A and 4B) mounted on the light-source circuit board **140** as the light sources **14** and the value of a current (current value) flowing each LED **111**, and also controls the supply power for the light sources **14**, so as to be able to improve power efficiency.

[0065] The display **12** includes a TFT-type display element **121** that forms the display light (first display light **L1** and second display light **L2**) representing a graphic of an arbitrary shape based on a signal sent from the display controller **151**, and a polarization control element **122** that switches the display light **L** emitted according to a signal sent from the display driver **152** between the first display light **L1** of the first polarization and the second display light **L2** of the second polarization. In the configuration of FIG. 5, for example, at the time of manual driving, the display driver **152** controls the polarization control element **122** so as to emit the first display light **L1** of the first polarization. At this time, the display controller **151** controls the display element **121** so as to generate the first display light **L1** that represents vehicle information, routing assistance information, a warning, etc. Further, for example, at the time of automatic driving, the display driver **152** performs the switching control of the polarization control element **122** so as to emit the second display light **L2** of the second polarization. At this time, the display controller **151** controls the display element **121** so as to generate the second display light **L2** that represents an assistant or agent supporting the driving by occupant **DR**, a character indicating the assistant or agent, etc.

[0066] Thus, in the HUD device **1A** according to the first embodiment of the present disclosure, when the virtual image **VI** is required to be displayed, the display **12** capable of controlling polarization sets the polarization condition of the backlight **11** (light sources **14**) to the first polarization condition (first polarization) to be reflected by the first mirror **131** of the imaging optical system **13**, so that the first display light **L1** is reflected by the third mirror **133** to enter the windshield **WS**, is reflected by the windshield **WS**, and forms the virtual image **VI** (see the first optical path **OP1** in FIG. 1) which can be displayed on the outer side of the windshield **WS** (an imaging region virtually set in front of the vehicle **C** so as to be inclined with respect to a road surface). On the other hand, when the real image **RI** is required to be displayed, the display **12** capable of controlling polarization sets the polarization condition of the backlight **11** (light sources **14**) to the second polarization condition (second polarization) to be transmitted through the first mirror **131** of the imaging optical system **13**, so that the second display light **L2** is reflected by the second mirror **132** to enter the third mirror **133**, is reflected by the third mirror **133** to enter the windshield **WS**, is reflected by the windshield **WS**, and forms the real image **RI** (see the second optical path **OP2** in FIG. 2) which can be displayed on the inner side of the windshield **WS** in front of the occupant **DR** (an imaging region virtually set so as to be vertical with respect to a road surface).

[0067] For example, in the imaging region of the virtual image **VI** angled less than 45 degrees with respect to the road surface, the display content appears to be developed on the road surface, and therefore, in a case where navigation or the like is performed, the display content appears to be superimposed on the road surface, which realizes advantage of intuitive information presentation. On the other hand, it is assumed that the imaging region of the real image **RI**, angled not less than

45 degrees with respect to the road surface, is used in a scene such as viewing entertainment contents during automatic driving or parking, and therefore displaying the real image RI upright with respect to the road surface realizes advantage of improved visibility.

[0068] Further in the controller **15**, the light source driver **153** controls the ON/OFF timing of each LED **111** (see FIGS. 3A, 3B, 4A and 4B) mounted on the light-source circuit board **140** as the light sources **14** and the value of a current (current value) flowing each LED **111**, and also controls the supply power for the light sources **14**, so as to be able to improve power efficiency. The light source driver **153** performs control such that an area of the light sources **14** to be turned-on more strongly than a predetermined intensity when the real image RI is to be displayed is made larger than an area of the light sources **14** turned-on more strongly than a predetermined intensity when the virtual image VI is displayed. In this connection, the “predetermined intensity” refers to an emission intensity of light, set in a default state, that is emitted from the backlight provided with the light sources mounted thereon to the display **12** when the virtual image VI or real image RI is to be displayed. In this embodiment, the level of the emission intensity is controlled based on the area of the light sources **14** to be turned on. Thus, when the real image RI is to be displayed, the control is performed in such a manner that the area of the light sources **14** to be turned-on more strongly than the predetermined intensity becomes larger than the area of the light sources **14** turned-on more strongly than the predetermined intensity for displaying the virtual image VI. In addition, the “area of the light sources to be turned-on” refers, for example, as depicted in FIG. **8** described later, to a mount area of the light sources to be turned-on (a turn-on area “A” upon generating virtual image, a turn-on area “B” upon generating real image) defined on the light-source circuit board **140** (backlight), among the plurality of light sources **14** mounted on the light-source circuit board **140**.
Operation of First Embodiment

[0069] Reference is made to FIG. **6**. FIG. **6** is a flowchart depicting an example of the operation of a control system, specifically the controller **15**, of the HUD device **1A** according to the first embodiment of the present disclosure. FIG. **8** is a diagram depicting an example of a first light-source turning-on pattern of the light sources **14** mounted on the backlight **11**, at the time of displaying the virtual image VI and the real image RI in the operation of FIG. **6**. Hereinafter, the operation of the control system (PGU **10**, mainly the controller **15**) of the HUD device **1A** depicted in FIG. **5** will be described in detail with reference to FIGS. **6** and **8**.

[0070] In the PGU **10**, the controller **15** (display driver **152**) first determines whether the vehicle C is in manual driving or in automatic driving, based on a signal sent from the switch **20** for changing the driving mode (manual driving, automatic driving) of the vehicle C (step ST**101**). If it is determined that the vehicle C is in the manual driving (step ST**101** “M”), the controller **15** (display controller **151**) controls the display element **121** of the display **12** to generate the first display light L**1** (virtual image VI) representing vehicle information, routing assistance information, a warning, and so forth (step ST**102**). At this time, the controller **15** (display driver **152**) controls the imaging optical system **13** in such a manner that the first display light L**1** of the first polarization is emitted via the polarization control element **122** of the display **12**. Thus, the display driver **152** switches the imaging optical system **13** so as to project the first display light L**1** from the emission port **17** toward the windshield WS through the first optical path OP**1** (step ST**103**).

[0071] Subsequently, the controller **15** (light source driver **153**) performs control to turn on at least a part of the LEDs **111** as the light sources **14** included in the backlight **11** (step ST**104**), and the display **12** emits (projects) the generated first display light L**1** (virtual image VI) toward the windshield WS through the imaging optical system **13** (first optical path OP**1**) and the emission port **17** (step ST**108**).

[0072] On the other hand, if the vehicle C is in the automatic driving (step ST**101** “A”), the controller **15** (display controller **151**) controls the display element **121** to generate the second display light L**2** representing an assistant or agent supporting the driving by occupant DR, a character indicating the assistant or agent, and so forth (step ST**105**). At this time, the controller **15**

(the display driver **152**) controls the imaging optical system **13** in such a manner that the second display light L2 of the second polarization is emitted via the polarization control element **122**. Thus, the display driver **152** performs control to switch the optical path of the imaging optical system **13** from the first optical path OP1 to the second optical path OP2 so as to project the second display light L2 from the emission port **17** toward the windshield WS via the second optical path OP2 (step ST106).

[0073] Subsequently, the controller **15** (light source driver **153**) performs control such that the area of the light sources **14** to be turned-on becomes larger than the area turned-on at the time of displaying the virtual image VI (step ST107). More specifically, as depicted in FIG. **8** for example, when the real image RI is to be displayed, the area of the light sources **14** mounted on the light-source circuit board **140** of the backlight **11** (turn-on area “B” upon generating real image), which are to be turned-on more strongly than a predetermined intensity, is made larger than the area of the light sources mounted on the light-source circuit board **140** (turn-on area “A” upon generating virtual image), which are turned-on more strongly than a predetermined intensity when the virtual image is displayed, along a long-side direction “H” of a rectangular region of the display **12**. On the other hand, when the display image is switched from the real image RI to the virtual image VI, for example, the light sources **14** mounted on outer periphery in the long-side direction of the rectangular region of the display **12**, used for displaying the real image VI, are controlled to be turned off.

[0074] Finally, the display **12** projects the generated second display light L2 (real image RI) toward the windshield WS as the projection member, via the imaging optical system **13** (second optical path OP2) and the emission port **17** (step ST108). As described above, the controller **15** performs the control such that, when the real image RI is to be displayed, the area of the light sources **14** to be turned-on more strongly than a predetermined intensity is made larger than the area of the light sources **14** turned-on more strongly than a predetermined intensity at the time of displaying the virtual image VI, and thereby makes it possible to suppress a disadvantage such that, when either one of the real image RI and the virtual image VI (e.g., real image) is displayed, light emitted from a pixel in a direction for displaying the other image (e.g., virtual image) is useless, and to improve light utilization efficiency. Therefore, it is possible to suppress a disadvantage such that, when either one of the real image RI and the virtual image VI is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve light utilization efficiency.

[0075] FIGS. **7A** and **7B** depict irradiation directions of light beams from each of a plurality of light sources **14** (LEDs **111** depicted in FIGS. **3A**, **3B**, **4A** and **4B**) mounted on the light-source circuit board **140** of the backlight **11** when viewing the light sources **14** from a normal direction, at the time of displaying the virtual image VI and the real image RI, respectively, in the HUD device **1A** according to the first embodiment of the present disclosure. When the display image is changed so as to switch from the virtual image VI to the real image RI, the controller **15** performs control such that, as depicted in FIG. **7B** for example, the light sources **14** (light beams indicated by solid arrows in the drawing) disposed at a mount region (i.e., outer peripheries Y1, Y2 of the light-source circuit board **140**) not overlapping with the display **12** when viewing the light-source circuit board **140** of the backlight **11** from a normal direction, on which the light sources **14** are mounted, are turned-on more strongly than the predetermined intensity, and thereby makes it possible to suppress a disadvantage such that, when either one of the real image RI and the virtual image VI (e.g., real image RI) is displayed, light emitted from a pixel in a direction for displaying the other image (e.g., virtual image VI) is useless, and to improve light utilization efficiency. Note that, in FIGS. **7A** and **7B**, a solid arrow indicates a light beam used for display, and a broken arrow indicates a light beam not used for display.

[0076] FIGS. **8** to **11** depict four examples of light-source turning-on patterns (first to fourth light-source turning-on patterns) of the plurality of light sources **14** mounted on the backlight **11**, at the time of displaying the virtual image V1 and the real image RI in the HUD device **1A** according to

the first embodiment of the present disclosure.

[0077] In the first light-source turning-on pattern depicted in FIG. 8, the controller 15 performs control such that, as depicted in FIG. 8 for example, the area of the light sources 14 mounted on the light-source circuit board 140 of the backlight 11 (turn-on area “B” upon generating real image), which are to be turned-on more strongly than a predetermined intensity when the real image is to be displayed, is made larger than the area of the light sources mounted on the light-source circuit board 140 (turn-on area “A” upon generating virtual image), which are turned-on more strongly than a predetermined intensity when the virtual image is displayed, along a long-side direction “H” of a rectangular region of the display 12. Alternatively, in the case of switching from a real image display to a virtual image display, control may be adopted such that, as depicted in FIG. 9 as the second light-source turning-on pattern for example, the light sources 14 on outer peripheries in a short-side direction “V” (upper and lower rows) of the turn-on area “B” upon generating real image are turned off.

[0078] In the third light-source turning-on pattern depicted in FIGS. 10A and 10B, the controller 15 performs control such that the area of the light sources 14 mounted on the light-source circuit board 140 of the backlight 11 (turn-on area “B” upon generating real image), which are to be turned-on more strongly than a predetermined intensity when the real image RI is to be displayed, is made larger than the area of the light sources 14 mounted on the light-source circuit board 140 (turn-on area “A” upon generating virtual image), which are turned-on more strongly than a predetermined intensity when the virtual image VI is displayed, along each of the long-side direction “H” and short-side direction “V” of the rectangular region of the display 12. Therefore, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and to improve light utilization efficiency. Not limited to the turning-on patterns of the light sources 14 depicted in FIGS. 10A and 10B, other control may be adopted such that: (1) all light sources 14 arranged on outer peripheries of the light-source circuit board 140 are turned off; (2) the light sources 14 arranged at one periphery are turned off; (3) one periphery of each of the long “H” and short “V” sides is turned off; (4) a part of the light sources 14 is turned off when displaying the real image and then the part of the light sources 14 turned-off for displaying the real image is turned on when displaying the virtual image, and so forth.

[0079] In the third light-source turn-on pattern depicted in FIGS. 10A and 10B, the controller 15 performs the control such that, when the real image RI is to be displayed, the area of the light sources 14 mounted on the light-source circuit board 140 of the backlight 11 (turn-on area “B” upon generating real image), which are to be turned-on more strongly than a predetermined intensity, is made larger than the area of the light sources 14 mounted on the light-source circuit board 140 (turn-on area “A” upon generating virtual image), which are turned-on more strongly than a predetermined intensity when the virtual image VI is displayed, along each of the long-side direction “H” and short-side direction “V” of the rectangular region of the display 12. In this connection, as a modified light-source turn-on pattern, the controller 15 may perform control such that an increment of the area of the light sources 14 made larger along the long-side direction H is larger than an increment of the area of the light sources 14 made larger along the short-side direction V, and thereby make it possible to suppress a disadvantage such that, when either one of the real image RI and the virtual image VI is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and to more effectively improve light utilization efficiency.

[0080] Also, as depicted in FIG. 11 as the fourth light-source turn-on pattern, the controller 15 may perform control such that all light sources of the backlight (turn-on area “A” upon generating virtual image) are turned on when displaying the real image RI and a part of the light sources 14 (turn-on area “B” upon generating real image surrounded by a broken line) mounted on the inner side of the light-source circuit board 140 except for outer peripheries along the short-side direction are turned off when displaying the virtual image VI.

[0081] As described above, the head-up display device **1A** according to the first embodiment is embodied as the head-up display device (HUD device **1A**) that, as depicted in FIGS. **1** and **2** for example, is provided with the emission port **17** and emits the display light **L** from the emission port **17** toward the projection member (windshield **WS**) so as to allow the virtual and real images of the display image represented by the display light **L** to be visually recognized. The HUD device **1A** includes the backlight **11** that includes a plurality of light sources **14** (FIGS. **7A** and **7B**) mounted thereon; the display **12** that transmits illumination light emitted from the light sources **14** and generates the display light **L**; the polarization control element **122** that switches between polarization conditions of the display light **L**; the imaging optical system **13** that causes the first display light **L1** of a first polarization condition to be emitted from the emission port **17** via the first optical path **OP1** having a first optical path-length to form the virtual image **VI**, and causes the second display light **L2** of a second polarization condition to be emitted from the emission port **17** via the second optical path **OP2** having a second optical path-length longer than the first optical path-length to form the real image **RI**; and the controller **15** that controls the polarization conditions of the display light **L** switched by the polarization control element **122** and turning on and off of each of the light sources **14**. The controller **15** performs the control such that, when the real image **RI** is to be displayed, the area of the light sources **14** to be turned-on more strongly than a predetermined intensity is made larger than the area of the light sources **14** turned-on more strongly than a predetermined intensity when the virtual image **VI** is displayed.

[0082] In the HUD device **1A** according to the first embodiment of the present disclosure, the controller **15** performs the control such that, when the real image **RI** is to be displayed, the area of the light sources **14** to be turned-on more strongly than a predetermined intensity is made larger than the area of the light sources **14** turned-on more strongly than a predetermined intensity when the virtual image **VI** is displayed. For example, performing control such that, when the real image is displayed, the outer periphery of the light source region is turned on, whereas when the virtual image is displayed, the outer periphery of the light source region, which is not visually recognized as the virtual image, is turned off, makes it possible to eliminate a difference in brightness between the time of displaying the real image **RI** and the time of displaying the virtual image **VI** while suppressing the generation of useless light, and thus to improve light utilization efficiency. In this way, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

[0083] Also in the HUD device **1A** according to the first embodiment of the present disclosure, when the display image is changed so as to switch from the virtual image **VI** to the real image **RI**, the controller **15** performs control such that, as depicted in FIG. **7B** for example, the light sources **14** (light beams indicated by solid arrows in the drawing) disposed at a mount region (i.e., outer peripheries **Y1**, **Y2** of the light-source circuit board **140**) not overlapping with the display **12** when viewing the light-source circuit board **140** of the backlight **11** from a normal direction, on which the light sources **14** are mounted, are turned-on more strongly than the predetermined intensity, and thereby makes it possible to suppress a disadvantage such that, when either one of the real image **RI** and the virtual image **VI** (e.g., real image **RI**) is displayed, light emitted from a pixel in a direction for displaying the other image (e.g., virtual image **VI**) is useless, and to improve light utilization efficiency.

[0084] Also in the HUD device **1A** according to the first embodiment of the present disclosure, the controller **15** performs control such that, as depicted in FIG. **8** for example, the area of the light sources **14** mounted on the light-source circuit board **140** of the backlight **11** (turn-on area “**B**” upon generating real image), which are to be turned-on more strongly than the predetermined intensity when the real image **RI** is to be displayed, is made larger than the area of the light sources **14** mounted on the light-source circuit board **140** (turn-on area “**A**” upon generating virtual image),

which are turned-on more strongly than the predetermined intensity when the virtual image VI is displayed, along a long-side direction “H” of a rectangular region of the display **12**. Alternatively, when changing a display from the real image RI to the virtual image VI, control may be adopted such that, as depicted in FIG. **9** for example, the light sources **14** on outer peripheries in a short-side direction “V” (upper and lower rows) of the turn-on area “B” upon generating real image are turned off. Due to the above, it is possible to suppress a disadvantage such that, when either one of the real image RI and the virtual image VI is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

[0085] Also in the HUD device **1A** according to the first embodiment of the present disclosure, the controller **15** performs control such that, as depicted in FIGS. **10A** and **10B** for example, the area of the light sources **14** mounted on the light-source circuit board **140** of the backlight **11** (turn-on area “B” upon generating real image), which are to be turned-on more strongly than the predetermined intensity when the real image RI is to be displayed, is made larger than the area of the light sources **14** mounted on the light-source circuit board **140** (turn-on area “A” upon generating virtual image), which are turned-on more strongly than the predetermined intensity when the virtual image VI is displayed, along each of the long-side direction “H” and short-side direction “V” of the rectangular region of the display **12**. Therefore, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and to improve light utilization efficiency. Not limited to the turning-on patterns of the light sources **14** depicted in FIGS. **10A** and **10B**, other control may be adopted such that: (1) all light sources **14** arranged on outer peripheries of the light-source circuit board **140** are turned off; (2) the light sources **14** arranged at one periphery are turned off; (3) one periphery of each of the long “H” and short “V” sides is turned off; (4) a part of the light sources **14** is turned off when displaying the real image RI and then the part of the light sources **14** turned-off for displaying the real image RI is turned on when displaying the virtual image VI, and so forth.

[0086] Also in the HUD device **1A** according to the first embodiment of the present disclosure, the controller **15** performs the control such that, as depicted in FIGS. **10A** and **10B** for example, when the real image RI is to be displayed, the area of the light sources **14** mounted on the light-source circuit board **140** of the backlight **11** (turn-on area “B” upon generating real image), which are to be turned-on more strongly than the predetermined intensity, is made larger than the area of the light sources **14** mounted on the light-source circuit board **140** (turn-on area “A” upon generating virtual image), which are turned-on more strongly than the predetermined intensity when the virtual image VI is displayed, along each of the long-side direction “H” and short-side direction “V” of the rectangular light-source circuit board **140** of the display **12**, and that an increment of the area of the light sources **14** made larger along the long-side direction H is larger than an increment of the area of the light sources **14** made larger along the short-side direction V, and thereby makes it possible to suppress a disadvantage such that, when either one of the real image RI and the virtual image VI is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and to more effectively improve light utilization efficiency.

[0087] A method of controlling a head-up display device according to the first embodiment of the present disclosure is embodied as a method of controlling the HUD device **1A** including, as depicted in FIGS. **1** and **2** for example, a backlight **11** that includes a light-source circuit board **140** provided with a plurality of light sources **14** mounted thereon; a display **12** that transmits illumination light from the light sources **14** of the backlight **11** and generates display light L; a polarization control element **122** that switches between polarization conditions of the display light L; an imaging optical system **13** that causes first display light L1 of a first polarization condition to be emitted from an emission port **17** via a first optical path OP1 having a first optical path-length to form a virtual image VI, and causes second display light L2 of a second polarization condition to be emitted from the emission port **17** via a second optical path OP2 having a second optical path-length longer than the first optical path-length to form a real image RI; and a controller **15** that

controls the polarization conditions of the display light L switched by the polarization control element **122** and turning on and off of each of the light sources **14** of the backlight **11**. The control method includes a step (see **ST106**) of switching, by the controller **15** of the HUD device **1A**, the imaging optical system **13** from the first optical path **OP1** to the second optical path **OP2** to change the display image from the virtual image **VI** to the real image **RI**; and a step (see **ST107**) of performing, by the controller **15**, control such that an area of the light sources **14** mounted on the light-source circuit board **140**, which are to be turned-on more strongly than a predetermined intensity when the real image **RI** is to be displayed, is made larger than an area of the light sources **14** turned-on more strongly than a predetermined intensity when the virtual image **VI** is displayed. [0088] In the control method of the HUD device **10A** according to the first embodiment of the present disclosure, the controller **15** executes the procedure (step **ST107**) of performing the control such that, when the real image **RI** is to be displayed, the area of the light sources **14** to be turned-on more strongly than the predetermined intensity is made larger than the area of the light sources **14** turned-on more strongly than the predetermined intensity when displaying the virtual image **VI**, and such that, for example, the outer periphery of the light source region is turned on when displaying the real image **RI**, and on the other hand, the outer periphery of the light source region, which is not visually recognized as the virtual image **VI**, is turned off when displaying the virtual image **VI**, so that it is possible to eliminate a difference in brightness between the time of displaying the real image and the time of displaying the virtual image while suppressing the generation of useless light, and thus to improve light utilization efficiency. Thus, it is possible to suppress a disadvantage such that, when either one of the real image **RI** and the virtual image **VI** is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

Configuration of Second Embodiment

[0089] FIG. **12** is a diagram depicting an example of a configuration of a HUD device **1B** according to a second embodiment of the present disclosure, which includes an imaging optical system. FIG. **13** is a diagram depicting an example of a configuration of a control system of the HUD device **1B** according to the second embodiment of the present disclosure, and FIG. **14** is a flowchart depicting an example of an operation of the control system of the HUD device **1B** according to the second embodiment of the present disclosure. Hereinafter, the configuration and operation of the HUD device **1B** according to the second embodiment of the present disclosure will be described in detail with reference to FIGS. **12** to **14**.

[0090] Reference is made to FIG. **12**. The HUD device **1B** according to the second embodiment depicted in FIG. **12** is different from the HUD device **1A** of the first embodiment depicted in FIGS. **1** and **2** in a configuration such that the HUD device **1B** of the second embodiment is provided with dual systems, each including the backlight **11**, the display **12** and the controller **15** included in the HUD device **1A** of the first embodiment, and thus, lenses of the imaging optical system **13** are optimally designed according to orientation characteristics required for displaying each of the real image **RI** and virtual image **VI**, and are independently controlled for displaying the real image **RI** and virtual image **VI** by dual-system controllers **15**.

[0091] The HUD device **1B** according to the second embodiment includes, as depicted in FIG. **12** for example, a first backlight **11a** that includes a plurality of first light sources mounted thereon; a first display **12a** that transmits illumination light from the first light sources and generates first display light **L1**; a second backlight **11b** that includes a plurality of second light sources mounted thereon; a second display **12b** that transmits illumination light from the second light sources and generates second display light **L2**; an imaging optical system **13** that causes the first display light **L1** of a first polarization condition to be emitted from an emission port **17** via a first optical path having a first optical path-length to form the virtual image **VI**, and causes the second display light **L2** of a second polarization condition to be emitted from the emission port **17** via a second optical path having a second optical path-length longer than the first optical path-length to form the real

image RI; a first controller **15a** that controls turning on and off of each of the first light sources; and a second controller **15b** that controls turning on and off of each of the second light sources. [0092] As depicted in FIG. **13** for example, the controllers **15a** and **15b** are included in dual-system picture generation units PGU-1 (PGU **10a**) and PGU-2 (PGU **10b**), respectively. The first controller **15a** performs control such that the first light sources are turned-on more strongly than a predetermined intensity when the virtual image VI is to be displayed by the first display light L1, and the second controller **15b** performs control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image RI is to be displayed by the second display light L2 is made larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image VI is displayed.

[0093] As depicted in FIG. **13** as a functional block diagram, the PGU-1 (PGU **10a**) includes the backlight **11a** (light sources **14**), the display **12a**, and the controller **15a**. The controller **15a** includes a display controller **155** that issues a command to the display **12a** so as to generate the first display light L1 (virtual image VI) representing a display image on the basis of, for example, information or signals sent from various devices **30**, such as a vehicle speed sensor, a navigation unit, RADAR, LiDAR, etc.; a display driver **156** that generates image by using the light emitted from the light sources **14** of the backlight **11** and drives a display element **121** on the basis of, for example, a signal sent from a switch **20** for changing a driving mode of the vehicle C (manual driving, automatic driving); and a light source driver **153** that controls supply power necessary for turning on and off the light sources **14** mounted on a light-source circuit board **140** (see FIGS. **7A** and **7B**) included in the backlight **11**. The light source driver **153** controls the ON/OFF timing of each LED **111** mounted on the light-source circuit board **140** as the light sources **14** and the value of a current (current value) flowing each LED **111**, and also controls the supply power for the light sources **14**, so as to be able to improve power efficiency.

[0094] The display **12a** includes a thin film transistor (TFT) type display element **121** that forms the first display light L1 representing a graphic of an arbitrary shape based on a signal sent from the controller **15a** (display controller **155**). For example, at the time of manual driving, the display driver **156** performs switching control, and at this time, the display controller **155** controls the display element **121** of the display **12a** so as to generate the first display light L1 (virtual image VI) representing vehicle information, routing assistance information, a warning, etc.

[0095] Although not depicted, the PGU-2 (PGU **10b**) has a configuration analogous to that of the PGU-1 (PGU **10a**) except for the controller **15b**, and includes the backlight **11b** (light sources **14B**), the display **12b** and the controller **15b** (all not depicted). The controller **15b** includes a light source driver **153**, a display controller **155**, and a display driver **156**. The display **12b** includes a TFT-type display element **121** that forms the second display light L2 representing a graphic of an arbitrary shape based on a signal sent from the controller **15b** (display controller **155**). For example, at the time of automatic driving, the display driver **156** performs switching control, and at this time, the display controller **155** controls the display element **121** so as to generate the second display light L2 (real image RI) that represents an assistant or agent supporting the driving by occupant DR, a character indicating the assistant or agent, etc.

[0096] The controller **15a** (light source driver **153**) of the PGU-1 (PGU **10a**) performs the control such that the light sources of the backlight **11** are turned-on more strongly than a predetermined intensity when the virtual image VI is to be displayed by the first display light L1, whereas the controller **15b** (light source driver **153**) of the PGU-2 (PGU **10b**) performs the control such that an area of the light sources **14B** of the backlight **11** to be turned-on more strongly than a predetermined intensity when the real image RI is to be displayed by the second display light L2 is made larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image VI is displayed.

Operation of Second Embodiment

[0097] Specifically, as depicted in FIG. **14** as a flowchart, the controller **15a** (display driver **152**)

determines whether the vehicle C is in manual driving or in automatic driving, based on a signal sent from the switch **20** for changing the driving mode (manual driving, automatic driving) of the vehicle C (step **ST201**). If it is determined that the vehicle C is in the manual driving (step **ST201** “M”), the controller **15a** (display controller **155**) controls the display element **121** of the display **12a** to generate the first display light **L1** (virtual image **VI**) representing vehicle information, routing assistance information, a warning, and so forth (step **ST202**). Subsequently, the controller **15a** (light source driver **153**) performs control to turn on at least a part of the LEDs **111** (e.g., front light) as the light sources **14** of the backlight **11** (step **ST203**), and the display **12a** emits the generated first display light **L1** (virtual image **VI**) from the emission port **17** via the first optical path having the first optical path-length (imaging optical system **13**) and projects the light toward the windshield **WS** (step **ST206**).

[0098] On the other hand, if the vehicle C is in the automatic driving (step **ST201** “A”), the controller **15b** (display controller **155**) controls the display element **121** of the display **12b** to generate the second display light **L2** (real image **RI**) representing an assistant or agent supporting the driving by occupant **DR**, a character indicating the assistant or agent, and so forth (step **ST204**). Subsequently, the controller **15b** (the light source driver **153**) performs control such that the area of the light sources **14** to be turned-on becomes larger than the area turned-on at the time of displaying the virtual image **VI** (step **ST205**). More specifically, as depicted in FIG. **8** for example, when the real image **RI** is to be displayed, the area of the light sources **14** mounted on the light-source circuit board **140** of the backlight **11b** (turn-on area “B” upon generating real image), which are to be turned-on more strongly than a predetermined intensity, is made larger than the area of the light sources mounted on the light-source circuit board **140** (turn-on area “A” upon generating virtual image), which are turned-on more strongly than a predetermined intensity when the virtual image **VI** is displayed, along a long-side direction “H” of the rectangular light-source circuit board **140** of the display **12b**. On the other hand, when the display image is switched from the real image **RI** to the virtual image **VI**, for example, the light sources **14** mounted on outer periphery in the long-side direction of the display **12b**, used for displaying the real image **VI**, are controlled to be turned off.

[0099] Finally, the display **12b** projects the generated display light **L2** (real image **VI**) toward the windshield **WS** via the second optical path (imaging optical system **13**) having the second optical path-length longer than the first optical path-length and the emission port **17** (step **ST206**).

[0100] As described above, the HUD device **1B** that includes dual systems for generating the virtual images **VI** and the real images **RI**, each including the light sources **14** of the backlight **11**, the display **12** and the controller **15**, and shares the imaging optical system **13**, has a configuration in which the first controller **15a** performs the control such that the first light sources of the backlight **11a** are turned-on more strongly than a predetermined intensity when the virtual image **VI** is to be displayed by the first display light **L1**, and the second controller **15b** performs the control such that an area of the second light sources to be turned-on more strongly than a predetermined intensity when the real image **RI** is to be displayed by the second display light **L2** is made larger than an area of the first light sources to be turned-on more strongly than the predetermined intensity when the virtual image **VI** is displayed. For example, performing control such that, when the real image **RI** is displayed, the outer periphery of the light source region is turned on, whereas when the virtual image **VI** is displayed, the outer periphery of the light source region, which is not visually recognized as the virtual image **VI**, is turned off, makes it possible to eliminate a difference in brightness between the time of displaying the real image **RI** and the time of displaying the virtual image **VI** while suppressing the generation of useless light, and thus to improve light utilization efficiency. In this way, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

Effects of Second Embodiment

[0101] As described above, the head-up display device according to the second embodiment of the present disclosure is embodied as the HUD device **1B** that, as depicted in FIG. **12** for example, is provided with the emission port **17** and emits the display light **L** from the emission port **17** toward the projection member (windshield **WS**) so as to allow the virtual image **VI** and real image **RI** of the display image represented by the display light **L** to be visually recognized. The HUD device **1B** includes the first backlight **11a** that includes a plurality of first light sources mounted thereon; the first display **12a** that transmits illumination light from the first light sources and generates the first display light **L1**; the second backlight **11b** that includes a plurality of second light sources mounted thereon; the second display **12b** that transmits illumination light from the second light sources and generates the second display light **L2**; the imaging optical system **13** that causes the first display light **L1** to be emitted from the emission port **17** via the first optical path having the first optical path-length to form the virtual image **VI**, and causes the second display light **L2** to be emitted from the emission port **17** via the second optical path having the second optical path-length longer than the first optical path-length to form the real image **RI**; the first controller **15a** that controls turning on and off of each of the first light sources; and the second controller **15b** that controls turning on and off of each of the second light sources. The first controller **15a** performs the control such that, when the virtual image **VI** is to be displayed by the first display light **L1**, the first light sources are turned-on more strongly than a predetermined intensity, and the second controller **15b** performs the control such that, when the real image **RI** is to be displayed by the second display light **L2**, an area of the light sources to be turned-on more strongly than a predetermined intensity is made larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image **VI** is displayed.

[0102] In the HUD device **1B** according to the second embodiment of the present disclosure, which is provided with dual systems for generating the virtual images **VI** and the real images **RI**, each including the light sources **14** of the backlight **11**, the display **12** and the controller **15**, and shares the imaging optical system **13**, the HUD device **1B** has a configuration for executing procedures (steps) in which the first controller **15a** performs the control such that the first light sources are turned-on more strongly than a predetermined intensity when the virtual image **VI** is to be displayed by the first display light **L1**, and the second controller **15b** performs the control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image **RI** is to be displayed by the second display light **L2** is made larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image **VI** is displayed. According to the above configuration, performing control such that, for example, the outer periphery of the light source region is turned on when the real image **RI** is displayed, whereas the outer periphery of the light source region, which is not visually recognized as the virtual image **VI**, is turned off when the virtual image **VI** is displayed, makes it possible to eliminate a difference in brightness between the time of displaying the real image **RI** and the time of displaying the virtual image **VI** while suppressing the generation of useless light, and thus to improve light utilization efficiency. Thus, it is possible to suppress a disadvantage such that, when either one of the real image **RI** and the virtual image **VI** is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

[0103] A method of controlling a head-up display device according to the second embodiment of the present disclosure is embodied as a method of controlling the HUD device **1B** including, as depicted in FIG. **12** for example, the emission port **17** and emitting the display light **L** from the emission port **17** toward the projection member (windshield **WS**) so as to allow the virtual image **VI** and real image **RI** of the display image represented by the display light **L** to be visually recognized, in which the HUD device **1B** includes the first backlight **11a** that includes a plurality of first light sources mounted thereon; the first display **12a** that transmits illumination light from the

first light sources and generates the first display light **L1**; the second backlight **11b** that includes a plurality of second light sources mounted thereon; the second display **12b** that transmits illumination light from the second light sources and generates the second display light **L2**; the imaging optical system **13** that causes the first display light **L1** to be emitted from the emission port **17** via the first optical path having the first optical path-length to form the virtual image **VI**, and causes the second display light **L2** to be emitted from the emission port **17** via the second optical path having the second optical path-length longer than the first optical path-length to form the real image **RI**; the first controller **15a** that controls turning on and off of each of the first light sources; and the second controller **15b** that controls turning on and off of each of the second light sources. The control method includes a step of performing, by the first controller **15a**, the control such that, when the virtual image **VI** is to be displayed by the first display light **L1**, the first light sources are turned-on more strongly than a predetermined intensity, and a step of performing, by the second controller **15b**, the control such that, when the real image **RI** is to be displayed by the second display light **L2**, an area of the light sources to be turned-on more strongly than a predetermined intensity is made larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image **VI** is displayed.

[0104] In the control method of the HUD device **1B** according to the second embodiment of the present disclosure, which is provided with dual systems for generating the virtual images **VI** and the real images **RI**, each including the light sources **14** of the backlight **11**, the display **12** and the controller **15**, and shares the imaging optical system **13**, the method has a configuration for executing procedures (steps) in which the first controller **15a** performs the control such that the first light sources are turned-on more strongly than a predetermined intensity when the virtual image **VI** is to be displayed by the first display light **L1**, and the second controller **15b** performs the control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image **RI** is to be displayed by the second display light **L2** is made larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image **VI** is displayed. According to the above procedure, performing control such that, for example, the outer periphery of the light source region is turned on when the real image **RI** is displayed, whereas the outer periphery of the light source region, which is not visually recognized as the virtual image **VI**, is turned off when the virtual image **VI** is displayed, makes it possible to eliminate a difference in brightness between the time of displaying the real image **RI** and the time of displaying the virtual image **VI** while suppressing the generation of useless light, and thus to improve light utilization efficiency. In this way, it is possible to suppress a disadvantage such that, when either one of the real image and the virtual image is displayed, light emitted from a pixel in a direction for displaying the other image is useless, and thus to improve the light utilization efficiency.

[0105] In the above embodiments of the present disclosure, the windshield **WS** is used as a light-transmissive member. However, a flat glass or a combiner may be used instead.

[0106] The present disclosure is not limited to the exemplary embodiments described above, and a person skilled in the art can readily modify the above exemplary embodiments within the scope of the following claims.

REFERENCE SIGNS LIST

[0107] **1** (**1A**, **1B**) . . . HEAD-UP DISPLAY DEVICE (HUD DEVICE) [0108] **10** . . . PICTURE GENERATION UNIT (PGU) [0109] **10a** . . . FIRST PICTURE GENERATION UNIT (PGU-1) [0110] **10b** . . . SECOND PICTURE GENERATION UNIT (PGU-2) [0111] **11** . . . BACKLIGHT [0112] **11a** . . . FIRST BACKLIGHT [0113] **11b** . . . SECOND BACKLIGHT [0114] **12** . . . DISPLAY [0115] **12a** . . . FIRST DISPLAY [0116] **12b** . . . SECOND DISPLAY [0117] **13** IMAGING OPTICAL SYSTEM [0118] **14** . . . LIGHT SOURCE [0119] **15** . . . CONTROLLER [0120] **15a** . . . FIRST CONTROLLER [0121] **15b** . . . SECOND CONTROLLER [0122] **17** . . . EMISSION PORT [0123] **20** . . . SWITCH [0124] **30** . . . VARIOUS DEVICES [0125] **131** . . .

FIRST MIRROR [0126] **132** . . . SECOND MIRROR [0127] **133** . . . THIRD MIRROR [0128] **121**
. . . DISPLAY ELEMENT [0129] **122** . . . POLARIZATION CONTROL ELEMENT [0130] **151** . .
. DISPLAY CONTROLLER [0131] **152** . . . DISPLAY DRIVER [0132] **153** . . . LIGHT-SOURCE
DRIVER [0133] **140** . . . LIGHT-SOURCE CIRCUIT BOARD [0134] RI . . . REAL IMAGE
[0135] VI . . . VIRTUAL IMAGE [0136] L1 . . . FIRST DISPLAY LIGHT [0137] L2 . . . SECOND
DISPLAY LIGHT [0138] OP1 . . . FIRST OPTICAL PATH [0139] OP2 . . . SECOND OPTICAL
PATH

Claims

1. A head-up display device provided with an emission port and emitting display light from the emission port toward a projection member so as to allow virtual and real images of a display image represented by the display light to be visually recognized, the head-up display device comprising: a backlight that includes a plurality of light sources mounted thereon; a display that transmits illumination light emitted from the light sources and generates the display light; a polarization control element that switches between polarization conditions of the display light; an imaging optical system that causes first display light of a first polarization condition to be emitted from the emission port via a first optical path having a first optical path-length to form the virtual image, and causes second display light of a second polarization condition to be emitted from the emission port via a second optical path having a second optical path-length longer than the first optical path-length to form the real image; and a controller that controls the polarization conditions of the display light switched by the polarization control element and turning on and off of each of the light sources, wherein the controller performs control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image is to be displayed is larger than an area of the light sources to be turned-on more strongly than a predetermined intensity when the virtual image is displayed.
2. The head-up display device of claim 1, wherein the controller further performs control such that, when the display image is changed so as to switch from the virtual image to the real image, a light source disposed at a mount region not overlapping with the display when viewing a light-source circuit board of the backlight from a normal direction, on which the light sources are mounted, is turned-on more strongly than the predetermined intensity.
3. The head-up display device of claim 1, wherein the controller performs control such that the area of the light sources mounted on a light-source circuit board of the backlight, which are to be turned-on more strongly than the predetermined intensity when the real image is to be displayed, is larger than the area of the light sources mounted on the light-source circuit board, which are turned-on more strongly than the predetermined intensity when the virtual image is displayed, along a long-side direction of a rectangular region of the display.
4. The head-up display device of claim 1, wherein the controller performs control such that the area of the light sources mounted on a light-source circuit board of the backlight, which are to be turned-on more strongly than the predetermined intensity when the real image is to be displayed, is larger than the area of the light sources mounted on the light-source circuit board, which are turned-on more strongly than the predetermined intensity when the virtual image is displayed, along each of long-side and short-side directions of a rectangular region of the display.
5. The head-up display device of claim 1, wherein the controller performs control such that the area of the light sources mounted on a light-source circuit board of the backlight, which are to be turned-on more strongly than the predetermined intensity when the real image is to be displayed, is larger than the area of the light sources mounted on the light-source circuit board, which are turned-on more strongly than the predetermined intensity when the virtual image is displayed, along each of long-side and short-side directions of a rectangular region of the display, and that an increment of the area of the light sources made larger along the long-side direction is larger than an

increment of the area of the light sources made larger along the short-side direction.

6. A head-up display device provided with an emission port and emitting display light from the emission port toward a projection member so as to allow virtual and real images of a display image represented by the display light to be visually recognized, the head-up display device comprising: a first backlight that includes a plurality of first light sources mounted thereon; a first display that transmits illumination light from the first light sources and generates first display light; a second backlight that includes a plurality of second light sources mounted thereon; a second display that transmits illumination light from the second light sources and generates second display light; an imaging optical system that causes the first display light to be emitted from the emission port via a first optical path having a first optical path-length to form the virtual image, and causes the second display light to be emitted from the emission port via a second optical path having a second optical path-length longer than the first optical path-length to form the real image; a first controller that controls turning on and off of each of the first light sources; and a second controller that controls turning on and off of each of the second light sources, wherein the first controller performs control such that the first light sources are turned-on more strongly than a predetermined intensity when the virtual image is to be displayed by the first display light, and wherein the second controller performs control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image is to be displayed by the second display light is larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image is displayed.

7. A method of controlling a head-up display device including a backlight that includes a light-source circuit board provided with a plurality of light sources mounted thereon; a display that transmits illumination light from the light sources of the backlight and generates display light; a polarization control element that switches between polarization conditions of the display light; an imaging optical system that causes first display light of a first polarization condition to be emitted from an emission port via a first optical path having a first optical path-length to form a virtual image, and causes second display light of a second polarization condition to be emitted from the emission port via a second optical path having a second optical path-length longer than the first optical path-length to form a real image; and a controller that controls the polarization conditions of the display light switched by the polarization control element and turning on and off of each of the light sources of the backlight, the method comprising: switching, by the controller, the imaging optical system from the first optical path to the second optical path to change a display image from the virtual image to the real image; and performing, by the controller, control such that an area of a light source region of the light sources mounted on the light-source circuit board, which are to be turned-on more strongly than a predetermined intensity when the real image is to be displayed, is larger than an area of a light source region of the light sources to be turned-on more strongly than a predetermined intensity when the virtual image is displayed.

8. A method of controlling a head-up display device provided with an emission port and emitting display light from the emission port toward a projection member so as to allow virtual and real images of a display image represented by the display light to be visually recognized, the head-up display device including a first backlight that includes a plurality of first light sources mounted thereon; a first display that transmits illumination light from the first light sources and generates first display light; a second backlight that includes a plurality of second light sources mounted thereon; a second display that transmits illumination light from the second light sources and generates second display light; an imaging optical system that causes the first display light to be emitted from the emission port via a first optical path having a first optical path-length to form the virtual image, and causes the second display light to be emitted from the emission port via a second optical path having a second optical path-length longer than the first optical path-length to form the real image; a first controller that controls turning on and off of each of the first light sources; and a second controller that controls turning on and off of each of the second light sources, the method

comprising: performing, by the first controller, control such that the first light sources are turned-on more strongly than a predetermined intensity when the virtual image is to be displayed by the first display light; and performing, by the second controller, control such that an area of the light sources to be turned-on more strongly than a predetermined intensity when the real image is to be displayed by the second display light is larger than an area of the light sources to be turned-on more strongly than the predetermined intensity when the virtual image is displayed.
