

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250274886

Kind Code

A1

Publication Date

August 28, 2025

Inventor(s)

ABOTABL; Ahmed Attia et al.

TECHNIQUES FOR ADAPTING TRANSMISSION OF WIRELESS COMMUNICATIONS BASED ON SYNCHRONIZATION SIGNAL BLOCK (SSB) INDICATION

Abstract

Aspects described herein relate to a user equipment (UE) receiving, from a network entity, an indication to modify a synchronization signal block (SSB) configuration in a first subset of a set of time periods, and transmitting, for the network entity and based on the indication, uplink control information (UCI) indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods. Other aspects relate to the network entity transmitting the indication and receiving the UCI.

Inventors: ABOTABL; Ahmed Attia (San Diego, CA), MAAMARI; Diana (San Diego, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 1000007738201

Appl. No.: 18/587419

Filed: February 26, 2024

Publication Classification

Int. Cl.: H04W56/00 (20090101); H04W72/1268 (20230101); H04W72/21 (20230101)

U.S. Cl.:

CPC H04W56/0015 (20130101); H04W72/1268 (20130101); H04W72/21 (20230101);

Background/Summary

FIELD OF THE DISCLOSURE

[0001] Aspects of the present disclosure relate generally to wireless communication systems, and more particularly, to transmitting uplink communications based on a synchronization signal block (SSB) configuration.

DESCRIPTION OF RELATED ART

[0002] Wireless communication systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be multiple-access systems capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). Examples of such multiple-access systems include code-division multiple access (CDMA) systems, time-division multiple access (TDMA) systems, frequency-division multiple access (FDMA) systems, and orthogonal frequency-division multiple access (OFDMA) systems, and single-carrier frequency division multiple access (SC-FDMA) systems.

[0003] These multiple access technologies have been adopted in various telecommunication standards to provide a common protocol that enables different wireless devices to communicate on a municipal, national, regional, and even global level. For example, a fifth generation (5G) wireless communications technology (which can be referred to as 5G new radio (5G NR)) is envisaged to expand and support diverse usage scenarios and applications with respect to current mobile network generations. In an aspect, 5G communications technology can include: enhanced mobile broadband addressing human-centric use cases for access to multimedia content, services and data; ultra-reliable-low latency communications (URLLC) with certain specifications for latency and reliability; and massive machine type communications, which can allow a very large number of connected devices and transmission of a relatively low volume of non-delay-sensitive information.

SUMMARY

[0004] The following presents a simplified summary of one or more aspects in order to provide a basic understanding of such aspects. This summary is not an extensive overview of all contemplated aspects, and is intended to neither identify key or critical elements of all aspects nor delineate the scope of any or all aspects. Its sole purpose is to present some concepts of one or more aspects in a simplified form as a prelude to the more detailed description that is presented later.

[0005] According to an aspect, an apparatus for wireless communication is provided that includes a transceiver, one or more memories configured to, individually or in combination, store instructions, and one or more processors communicatively coupled with the one or more memories. The one or more processors are, individually or in combination, configured to execute the instructions to cause the apparatus to receive, from a network entity, an indication to modify a synchronization signal block (SSB) configuration in a first subset of a set of time periods, and transmit, for the network entity and based on the indication, uplink control information (UCI) indicating whether the apparatus is to transmit uplink communications in a second subset of the set of time periods.

[0006] In another aspect, an apparatus for wireless communication is provided that includes a transceiver, one or more memories configured to, individually or in combination, store instructions, and one or more processors communicatively coupled with the one or more memories. The one or more processors are, individually or in combination, configured to execute the instructions to cause the apparatus to transmit, for a user equipment (UE), an indication to modify a SSB configuration in a first subset of set of time periods, and receive, for the UE and based on the indication, UCI indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods.

[0007] In another aspect, a method for wireless communication at a UE is provided that includes receiving, from a network entity, an indication to modify a SSB configuration in a first subset of a set of time periods, and transmitting, for the network entity and based on the indication, UCI

indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods.

[0008] In another aspect, a method for wireless communication at a network entity is provided that includes transmitting, for a UE, an indication to modify a SSB configuration in a first subset of set of time periods, and receiving, for the UE and based on the indication, UCI indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods.

[0009] In a further aspect, an apparatus for wireless communication is provided that includes a transceiver, a memory configured to store instructions, and one or more processors communicatively coupled with the transceiver and the memory. The one or more processors are configured to execute the instructions to perform the operations of methods described herein. In another aspect, an apparatus for wireless communication is provided that includes means for performing the operations of methods described herein. In yet another aspect, a computer-readable medium is provided including code executable by one or more processors to perform the operations of methods described herein.

[0010] To the accomplishment of the foregoing and related ends, the one or more aspects comprise the features hereinafter fully described and particularly pointed out in the claims. The following description and the annexed drawings set forth in detail certain illustrative features of the one or more aspects. These features are indicative, however, of but a few of the various ways in which the principles of various aspects may be employed, and this description is intended to include all such aspects and their equivalents.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0011] The disclosed aspects will hereinafter be described in conjunction with the appended drawings, provided to illustrate and not to limit the disclosed aspects, wherein like designations denote like elements, and in which:

[0012] FIG. 1 illustrates an example of a wireless communication system, in accordance with various aspects described herein;

[0013] FIG. 2 is a diagram illustrating an example of disaggregated base station architecture, in accordance with various aspects described herein;

[0014] FIG. 3 is a block diagram illustrating an example of a user equipment (UE), in accordance with various aspects described herein;

[0015] FIG. 4 is a block diagram illustrating an example of a base station, in accordance with various aspects described herein;

[0016] FIG. 5 is a flow chart illustrating an example of a method for transmitting uplink control information (UCI) indicating whether a UE is transmitting uplink communications based on a received indication of synchronization signal block (SSB) configuration modification, in accordance with aspects described herein;

[0017] FIG. 6 is a flow chart illustrating an example of a method for transmitting an indication of modifying a SSB configuration, in accordance with aspects described herein;

[0018] FIG. 7 illustrates examples of timelines where the indication to modify a SSB configuration is received before transmitting UCI indicating whether the UE is transmitting uplink communications, in accordance with aspects described herein;

[0019] FIG. 8 illustrates examples of timelines where the indication to modify a SSB configuration is received and considered before transmitting UCI indicating whether the UE is transmitting uplink communications, in accordance with aspects described herein;

[0020] FIG. 9 illustrates an example of a timeline where the indication to modify a SSB configuration is received and considered after transmitting UCI indicating whether the UE is

transmitting uplink communications, in accordance with aspects described herein; and [0021] FIG. 10 is a block diagram illustrating an example of a MIMO communication system including a base station and a UE, in accordance with various aspects described herein.

DETAILED DESCRIPTION

[0022] Various aspects are now described with reference to the drawings. In the following description, for purposes of explanation, numerous specific details are set forth in order to provide a thorough understanding of one or more aspects. It may be evident, however, that such aspect(s) may be practiced without these specific details.

[0023] The described features generally relate to adapting uplink transmissions based on a synchronization signal block (SSB) configuration or modifications to the SSB configuration. For example, in fifth generation (5G) new radio (NR) or other wireless communication technologies, a network node, such as a base station, gNB, etc., can schedule a user equipment (UE) with resources for transmitting uplink communications to the network (e.g., to the network node or one or more other network nodes). In addition, the network node can configure the UE with resources over which to receive SSBs from the network (e.g., from the network node or one or more other network nodes). The network node can transmit SSBs, which can include a primary synchronization signal (PSS), secondary synchronization signal (SSS), and physical broadcast channel (PBCH), to assist UEs in synchronizing with the network, measuring and/or reporting signal measurements of the SSB signals, selecting beams for beamforming antenna resources to transmit or receive communications, etc.

[0024] In 5G NR, the network can adapt SSB transmission in the time domain, e.g., adapt periodicity of SSB transmission, to provide energy savings for the network. In one example, the network can adapt the SSB transmission periodicity using broadcast signaling by a network node (e.g., a system information block (SIB) 1), which can be received and processed by UEs within range of the network node. In some examples, the network node can transmit an indication to adapt (e.g., modify) the SSB configuration, which can include transmitting a media access control (MAC)-control element (CE), downlink control information (DCI) (e.g., in physical downlink control channel (PDCCH) or physical downlink shared channel (PDSCH), etc.), and/or the like, such indication may allow for achieving high energy efficiency and may result in minimal impact on legacy UEs and/or UE latency.

[0025] In addition, in 5G NR, the network can configure the UE with resources for transmitting uplink communications (e.g., physical uplink control channel (PUCCH), physical uplink shared channel (PUSCH), etc.) using a configured grant (CG). In this example, the network can indicate, to the UE, scheduling parameters for multiple PUSCH occasions (e.g., by indicating a starting resource and periodicity). The UE can accordingly receive the CG and transmit uplink communications during valid PUSCH occasions indicated by the CG (and using a frequency resource allocation indicated by the CG). In addition, in this example, the UE can send, to the network, uplink transmission opportunity (UTO)-uplink control information (UCI) to indicate PUSCH occasions that are or are not used by the UE for uplink transmissions. For example, the UTO-UCI can include a bitmap of bits where each bit can indicate whether the UE plans to transmit uplink communications in an associated upcoming valid PUSCH occasion. This can allow the UE to skip or cancel uplink transmission in certain PUSCH occasions, and the network can conserve energy by not attempting to receive or process uplink transmissions over the skipped PUSCH occasions.

[0026] The bits in the UTO-UCI can refer to valid PUSCH occasions, which may not necessarily include all PUSCH occasions configured by the CG. For example, if the PUSCH occasion overlaps with a semi-statically configured downlink resource (e.g., symbol) or SSB, this PUSCH occasion may not be considered as a valid PUSCH occasion, and thus the UTO-UCI bitmap may not need to include a bit for such PUSCH occasions. Aspects described herein relate to whether the UE considers a PUSCH occasion as a valid PUSCH occasion when the network modifies the SSB

configuration. Certain aspects relate to UE functionality when the UE receives an indication adapting or modifying SSBs in the time domain before the UE sends the UTO-UCI, and other aspects relate to UE functionality when the UE receives an indication adapting or modifying SSBs in the time domain after the UE sends the UTO-UCI.

[0027] Thus, in accordance with aspects described herein, the UE can effectively communicate UTO-UCI to the network even when the network modifies the SSB configuration, which may result in some PUSCH occasions becoming invalid. This can improve quality of communications between the UE and the network and avoid missed communication opportunities or retransmissions where the UE may otherwise transmit, or indicate transmission in UTO-UCI of, uplink communications in occasions where the network is transmitting SSB.

[0028] The described features will be presented in more detail below with reference to FIGS. 1-10.

[0029] As used in this application, the terms “component,” “module,” “system” and the like are intended to include a computer-related entity, such as but not limited to hardware, firmware, a combination of hardware and software, software, or software in execution. For example, a component may be, but is not limited to being, a process running on a processor, a processor, an object, an executable, a thread of execution, a program, and/or a computer. By way of illustration, both an application running on a computing device and the computing device can be a component. One or more components can reside within a process and/or thread of execution and a component can be localized on one computer and/or distributed between two or more computers. In addition, these components can execute from various computer readable media having various data structures stored thereon. The components can communicate by way of local and/or remote processes such as in accordance with a signal having one or more data packets, such as data from one component interacting with another component in a local system, distributed system, and/or across a network such as the Internet with other systems by way of the signal.

[0030] As used herein, a processor, at least one processor, and/or one or more processors, individually or in combination, configured to perform or operable for performing a plurality of actions is meant to include at least two different processors able to perform different, overlapping or non-overlapping subsets of the plurality actions, or a single processor able to perform all of the plurality of actions. In one non-limiting example of multiple processors being able to perform different ones of the plurality of actions in combination, a description of a processor, at least one processor, and/or one or more processors configured or operable to perform actions X, Y, and Z may include at least a first processor configured or operable to perform a first subset of X, Y, and Z (e.g., to perform X) and at least a second processor configured or operable to perform a second subset of X, Y, and Z (e.g., to perform Y and Z). Alternatively, a first processor, a second processor, and a third processor may be respectively configured or operable to perform a respective one of actions X, Y, and Z. It should be understood that any combination of one or more processors each may be configured or operable to perform any one or any combination of a plurality of actions.

[0031] As used herein, a memory, at least one memory, and/or one or more memories, individually or in combination, configured to store or having stored thereon instructions executable by one or more processors for performing a plurality of actions is meant to include at least two different memories able to store different, overlapping or non-overlapping subsets of the instructions for performing different, overlapping or non-overlapping subsets of the plurality actions, or a single memory able to store the instructions for performing all of the plurality of actions. In one non-limiting example of one or more memories, individually or in combination, being able to store different subsets of the instructions for performing different ones of the plurality of actions, a description of a memory, at least one memory, and/or one or more memories configured or operable to store or having stored thereon instructions for performing actions X, Y, and Z may include at least a first memory configured or operable to store or having stored thereon a first subset of instructions for performing a first subset of X, Y, and Z (e.g., instructions to perform X) and at least a second memory configured or operable to store or having stored thereon a second

subset of instructions for performing a second subset of X, Y, and Z (e.g., instructions to perform Y and Z). Alternatively, a first memory, and second memory, and a third memory may be respectively configured to store or have stored thereon a respective one of a first subset of instructions for performing X, a second subset of instruction for performing Y, and a third subset of instructions for performing Z. It should be understood that any combination of one or more memories each may be configured or operable to store or have stored thereon any one or any combination of instructions executable by one or more processors to perform any one or any combination of a plurality of actions. Moreover, one or more processors may each be coupled to at least one of the one or more memories and configured or operable to execute the instructions to perform the plurality of actions. For instance, in the above non-limiting example of the different subset of instructions for performing actions X, Y, and Z, a first processor may be coupled to a first memory storing instructions for performing action X, and at least a second processor may be coupled to at least a second memory storing instructions for performing actions Y and Z, and the first processor and the second processor may, in combination, execute the respective subset of instructions to accomplish performing actions X, Y, and Z. Alternatively, three processors may access one of three different memories each storing one of instructions for performing X, Y, or Z, and the three processor may in combination execute the respective subset of instruction to accomplish performing actions X, Y, and Z. Alternatively, a single processor may execute the instructions stored on a single memory, or distributed across multiple memories, to accomplish performing actions X, Y, and Z.

[0032] Techniques described herein may be used for various wireless communication systems such as CDMA, TDMA, FDMA, OFDMA, single carrier-FDMA, and other systems. The terms “system” and “network” may often be used interchangeably. A CDMA system may implement a radio technology such as CDMA2000, Universal Terrestrial Radio Access (UTRA), etc. CDMA2000 covers IS-2000, IS-95, and IS-856 standards. IS-2000 Releases 0 and A are commonly referred to as CDMA2000 1X, 1X, etc. IS-856 (TIA-856) is commonly referred to as CDMA2000 1xEV-DO, High Rate Packet Data (HRPD), etc. UTRA includes Wideband CDMA (WCDMA) and other variants of CDMA. A TDMA system may implement a radio technology such as Global System for Mobile Communications (GSM). An OFDMA system may implement a radio technology such as Ultra Mobile Broadband (UMB), Evolved UTRA (E-UTRA), IEEE 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM™, etc. UTRA and E-UTRA are part of Universal Mobile Telecommunication System (UMTS). 3GPP Long Term Evolution (LTE) and LTE-Advanced (LTE-A) are new releases of UMTS that use E-UTRA. UTRA, E-UTRA, UMTS, LTE, LTE-A, and GSM are described in documents from an organization named “3rd Generation Partnership Project” (3GPP). CDMA2000 and UMB are described in documents from an organization named “3rd Generation Partnership Project 2” (3GPP2). The techniques described herein may be used for the systems and radio technologies mentioned above as well as other systems and radio technologies, including cellular (e.g., LTE) communications over a shared radio frequency spectrum band. The description below, however, describes an LTE/LTE-A system for purposes of example, and LTE terminology is used in much of the description below, although the techniques are applicable beyond LTE/LTE-A applications (e.g., to fifth generation (5G) new radio (NR) networks or other next generation communication systems).

[0033] The following description provides examples, and is not limiting of the scope, applicability, or examples set forth in the claims. Changes may be made in the function and arrangement of elements discussed without departing from the scope of the disclosure. Various examples may omit, substitute, or add various procedures or components as appropriate. For instance, the methods described may be performed in an order different from that described, and various steps may be added, omitted, or combined. Also, features described with respect to some examples may be combined in other examples.

[0034] Various aspects or features will be presented in terms of systems that can include a number of devices, components, modules, and the like. It is to be understood and appreciated that the

various systems can include additional devices, components, modules, etc. and/or may not include all of the devices, components, modules etc. discussed in connection with the figures. A combination of these approaches can also be used.

[0035] FIG. 1 is a diagram illustrating an example of a wireless communications system and an access network **100**. The wireless communications system (also referred to as a wireless wide area network (WWAN)) can include base stations **102**, UEs **104**, an Evolved Packet Core (EPC) **160**, and/or a 5G Core (5GC) **190**. The base stations **102** may include macro cells (high power cellular base station) and/or small cells (low power cellular base station). The macro cells can include base stations. The small cells can include femtocells, picocells, and microcells. In an example, the base stations **102** may also include gNBs **180**, as described further herein. In one example, some nodes of the wireless communication system may have a modem **340** and UE communicating component **342** for transmitting UCI indicating whether the UE is transmitting uplink communications based on a received indication of SSB configuration modification, in accordance with aspects described herein. In addition, some nodes may have a modem **440** and BS communicating component **442** for indicating modification of SSB configuration, in accordance with aspects described herein. Though a UE **104** is shown as having the modem **340** and UE communicating component **342** and a base station **102**/gNB **180** is shown as having the modem **440** and BS communicating component **442**, this is one illustrative example, and substantially any node or type of node may include a modem **340** and UE communicating component **342** and/or a modem **440** and BS communicating component **442** for providing corresponding functionalities described herein.

[0036] The base stations **102** configured for 4G LTE (which can collectively be referred to as Evolved Universal Mobile Telecommunications System (UMTS) Terrestrial Radio Access Network (E-UTRAN)) may interface with the EPC **160** through backhaul links **132** (e.g., using an S1 interface). The base stations **102** configured for 5G NR (which can collectively be referred to as Next Generation RAN (NG-RAN)) may interface with 5GC **190** through backhaul links **184**. In addition to other functions, the base stations **102** may perform one or more of the following functions: transfer of user data, radio channel ciphering and deciphering, integrity protection, head compression, mobility control functions (e.g., handover, dual connectivity), inter-cell interference coordination, connection setup and release, load balancing, distribution for non-access stratum (NAS) messages, NAS node selection, synchronization, radio access network (RAN) sharing, multimedia broadcast multicast service (MBMS), subscriber and equipment trace, RAN information management (RIM), paging, positioning, and delivery of warning messages. The base stations **102** may communicate directly or indirectly (e.g., through the EPC **160** or 5GC **190**) with each other over backhaul links **134** (e.g., using an X2 interface). The backhaul links **134** may be wired or wireless.

[0037] The base stations **102** may wirelessly communicate with one or more UEs **104**. Each of the base stations **102** may provide communication coverage for a respective geographic coverage area **110**. There may be overlapping geographic coverage areas **110**. For example, the small cell **102'** may have a coverage area **110'** that overlaps the coverage area **110** of one or more macro base stations **102**. A network that includes both small cell and macro cells may be referred to as a heterogeneous network. A heterogeneous network may also include Home Evolved Node Bs (eNBs) (HeNBs), which may provide service to a restricted group, which can be referred to as a closed subscriber group (CSG). The communication links **120** between the base stations **102** and the UEs **104** may include uplink (UL) (also referred to as reverse link) transmissions from a UE **104** to a base station **102** and/or downlink (DL) (also referred to as forward link) transmissions from a base station **102** to a UE **104**. The communication links **120** may use multiple-input and multiple-output (MIMO) antenna technology, including spatial multiplexing, beamforming, and/or transmit diversity. The communication links may be through one or more carriers. The base stations **102**/UEs **104** may use spectrum up to Y MHz (e.g., 5, 10, 15, 20, 100, 400, etc. MHz) bandwidth per carrier allocated in a carrier aggregation of up to a total of Yx MHz (e.g., for x component

carriers) used for transmission in the DL and/or the UL direction. The carriers may or may not be adjacent to each other. Allocation of carriers may be asymmetric with respect to DL and UL (e.g., more or less carriers may be allocated for DL than for UL). The component carriers may include a primary component carrier and one or more secondary component carriers. A primary component carrier may be referred to as a primary cell (PCell) and a secondary component carrier may be referred to as a secondary cell (SCell).

[0038] In another example, certain UEs **104** may communicate with each other using device-to-device (D2D) communication link **158**. The D2D communication link **158** may use the DL/UL WWAN spectrum. The D2D communication link **158** may use one or more sidelink channels, such as a physical sidelink broadcast channel (PSBCH), a physical sidelink discovery channel (PSDCH), a physical sidelink shared channel (PSSCH), and a physical sidelink control channel (PSCCH). D2D communication may be through a variety of wireless D2D communications systems, such as for example, FlashLinQ, WiMedia, Bluetooth, ZigBee, Wi-Fi based on the IEEE 802.11 standard, LTE, or NR.

[0039] The wireless communications system may further include a Wi-Fi access point (AP) **150** in communication with Wi-Fi stations (STAs) **152** via communication links **154** in a 5 GHz unlicensed frequency spectrum. When communicating in an unlicensed frequency spectrum, the STAs **152**/AP **150** may perform a clear channel assessment (CCA) prior to communicating in order to determine whether the channel is available.

[0040] The small cell **102'** may operate in a licensed and/or an unlicensed frequency spectrum. When operating in an unlicensed frequency spectrum, the small cell **102'** may employ NR and use the same 5 GHz unlicensed frequency spectrum as used by the Wi-Fi AP **150**. The small cell **102'**, employing NR in an unlicensed frequency spectrum, may boost coverage to and/or increase capacity of the access network.

[0041] A base station **102**, whether a small cell **102'** or a large cell (e.g., macro base station), may include an eNB, gNodeB (gNB), or other type of base station. Some base stations, such as gNB **180** may operate in a traditional sub 6 GHz spectrum, in millimeter wave (mmW) frequencies, and/or near mmW frequencies in communication with the UE **104**. When the gNB **180** operates in mmW or near mmW frequencies, the gNB **180** may be referred to as an mmW base station. Extremely high frequency (EHF) is part of the RF in the electromagnetic spectrum. EHF has a range of 30 GHz to 300 GHz and a wavelength between 1 millimeter and 10 millimeters. Radio waves in the band may be referred to as a millimeter wave. Near mmW may extend down to a frequency of 3 GHz with a wavelength of 100 millimeters. The super high frequency (SHF) band extends between 3 GHz and 30 GHz, also referred to as centimeter wave. Communications using the mmW/near mmW radio frequency band has extremely high path loss and a short range. The mmW base station **180** may utilize beamforming **182** with the UE **104** to compensate for the extremely high path loss and short range. A base station **102** referred to herein can include a gNB **180**.

[0042] The EPC **160** may include a Mobility Management Entity (MME) **162**, other MMEs **164**, a Serving Gateway **166**, a Multimedia Broadcast Multicast Service (MBMS) Gateway **168**, a Broadcast Multicast Service Center (BM-SC) **170**, and a Packet Data Network (PDN) Gateway **172**. The MME **162** may be in communication with a Home Subscriber Server (HSS) **174**. The MME **162** is the control node that processes the signaling between the UEs **104** and the EPC **160**. Generally, the MME **162** provides bearer and connection management. All user Internet protocol (IP) packets are transferred through the Serving Gateway **166**, which itself is connected to the PDN Gateway **172**. The PDN Gateway **172** provides UE IP address allocation as well as other functions. The PDN Gateway **172** and the BM-SC **170** are connected to the IP Services **176**. The IP Services **176** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a PS Streaming Service, and/or other IP services. The BM-SC **170** may provide functions for MBMS user service provisioning and delivery. The BM-SC **170** may serve as an entry point for content provider MBMS transmission, may be used to authorize and initiate MBMS Bearer Services within a public

land mobile network (PLMN), and may be used to schedule MBMS transmissions. The MBMS Gateway **168** may be used to distribute MBMS traffic to the base stations **102** belonging to a Multicast Broadcast Single Frequency Network (MBSFN) area broadcasting a particular service, and may be responsible for session management (start/stop) and for collecting eMBMS related charging information.

[0043] The 5GC **190** may include an Access and Mobility Management Function (AMF) **192**, other AMFs **193**, a Session Management Function (SMF) **194**, and a User Plane Function (UPF) **195**.

The AMF **192** may be in communication with a Unified Data Management (UDM) **196**. The AMF **192** can be a control node that processes the signaling between the UEs **104** and the 5GC **190**.

Generally, the AMF **192** can provide QoS flow and session management. User Internet protocol (IP) packets (e.g., from one or more UEs **104**) can be transferred through the UPF **195**. The UPF **195** can provide UE IP address allocation for one or more UEs, as well as other functions. The UPF **195** is connected to the IP Services **197**. The IP Services **197** may include the Internet, an intranet, an IP Multimedia Subsystem (IMS), a PS Streaming Service, and/or other IP services.

[0044] The base station may also be referred to as a gNB, Node B, evolved Node B (eNB), an access point, a base transceiver station, a radio base station, a radio transceiver, a transceiver function, a basic service set (BSS), an extended service set (ESS), a transmit reception point (TRP), or some other suitable terminology. The base station **102** provides an access point to the EPC **160** or 5GC **190** for a UE **104**. Examples of UEs **104** include a cellular phone, a smart phone, a session initiation protocol (SIP) phone, a laptop, a personal digital assistant (PDA), a satellite radio, a global positioning system, a multimedia device, a video device, a digital audio player (e.g., MP3 player), a camera, a game console, a tablet, a smart device, a wearable device, a vehicle, an electric meter, a gas pump, a large or small kitchen appliance, a healthcare device, an implant, a sensor/actuator, a display, or any other similar functioning device. Some of the UEs **104** may be referred to as IoT devices (e.g., parking meter, gas pump, toaster, vehicles, heart monitor, etc.). IoT UEs may include machine type communication (MTC)/enhanced MTC (eMTC, also referred to as category (CAT)-M, Cat M1) UEs, NB-IoT (also referred to as CAT NB1) UEs, as well as other types of UEs. As described herein, eMTC and NB-IoT may refer to future technologies that may evolve from or may be based on these technologies. For example, eMTC may include FeMTC (further eMTC), eFeMTC (enhanced further eMTC), mMTC (massive MTC), etc., and NB-IoT may include eNB-IoT (enhanced NB-IoT), FeNB-IoT (further enhanced NB-IoT), etc. The UE **104** may also be referred to as a station, a mobile station, a subscriber station, a mobile unit, a subscriber unit, a wireless unit, a remote unit, a mobile device, a wireless device, a wireless communications device, a remote device, a mobile subscriber station, an access terminal, a mobile terminal, a wireless terminal, a remote terminal, a handset, a user agent, a mobile client, a client, or some other suitable terminology.

[0045] Deployment of communication systems, such as 5G new radio (NR) systems, may be arranged in multiple manners with various components or constituent parts. In a 5G NR system, or network, a network node, a network entity, a mobility element of a network, a radio access network (RAN) node, a core network node, a network element, or a network equipment, such as a base station (BS, e.g., BS **102**), or one or more units (or one or more components) performing base station functionality, may be implemented in an aggregated or disaggregated architecture. For example, a BS (such as a Node B (NB), evolved NB (eNB), NR BS, 5G NB, access point (AP), a transmit receive point (TRP), or a cell, etc.) may be implemented as an aggregated base station (also known as a standalone BS or a monolithic BS) or a disaggregated base station.

[0046] An aggregated base station may be configured to utilize a radio protocol stack that is physically or logically integrated within a single RAN node. A disaggregated base station may be configured to utilize a protocol stack that is physically or logically distributed among two or more units (such as one or more central or centralized units (CUs), one or more distributed units (DUs), or one or more radio units (RUs)). In some aspects, a CU may be implemented within a RAN node,

and one or more DUs may be co-located with the CU, or alternatively, may be geographically or virtually distributed throughout one or multiple other RAN nodes. The DUs may be implemented to communicate with one or more RUs. Each of the CU, DU and RU also can be implemented as virtual units, i.e., a virtual central unit (VCU), a virtual distributed unit (VDU), or a virtual radio unit (VRU).

[0047] Base station-type operation or network design may consider aggregation characteristics of base station functionality. For example, disaggregated base stations may be utilized in an integrated access backhaul (IAB) network, an open radio access network (O-RAN (such as the network configuration sponsored by the O-RAN Alliance)), or a virtualized radio access network (vRAN, also known as a cloud radio access network (C-RAN)). Disaggregation may include distributing functionality across two or more units at various physical locations, as well as distributing functionality for at least one unit virtually, which can enable flexibility in network design. The various units of the disaggregated base station, or disaggregated RAN architecture, can be configured for wired or wireless communication with at least one other unit.

[0048] In an example, BS communicating component **442** can transmit, for one or more UEs **104**, an indication to modify a SSB configuration in at least a portion of a set of time periods. For example, the time periods may correspond to one or more symbols (e.g., orthogonal frequency division multiplexing (OFDM) symbols, single carrier-frequency division multiplexing (SC-FDM) symbols, and/or the like), one or more slots of multiple symbols, or other time divisions defined in a wireless communication technology, such as 5G NR. In an example, UE communicating component **342** can transmit, for the base station **102**, UCI indicating whether valid PUSCH occasions are used for uplink transmissions, and can determine which PUSCH occasions are valid and indicated in the UCI based on the indication to modify the SSB configuration and/or based on when the indication is received.

[0049] FIG. 2 shows a diagram illustrating an example of disaggregated base station **200** architecture. The disaggregated base station **200** architecture may include one or more central units (CUs) **210** that can communicate directly with a core network **220** via a backhaul link, or indirectly with the core network **220** through one or more disaggregated base station units (such as a Near-Real Time (Near-RT) RAN Intelligent Controller (RIC) **225** via an E2 link, or a Non-Real Time (Non-RT) RIC **215** associated with a Service Management and Orchestration (SMO) Framework **205**, or both). A CU **210** may communicate with one or more distributed units (DUs) **230** via respective midhaul links, such as an F1 interface. The DUs **230** may communicate with one or more radio units (RUs) **240** via respective fronthaul links. The RUs **240** may communicate with respective UEs **104** via one or more radio frequency (RF) access links. In some implementations, the UE **104** may be simultaneously served by multiple RUs **240**.

[0050] Each of the units, e.g., the CUs **210**, the DUs **230**, the RUs **240**, as well as the Near-RT RICs **225**, the Non-RT RICs **215** and the SMO Framework **205**, may include one or more interfaces or be coupled to one or more interfaces configured to receive or transmit signals, data, or information (collectively, signals) via a wired or wireless transmission medium. Each of the units, or an associated processor or controller providing instructions to the communication interfaces of the units, can be configured to communicate with one or more of the other units via the transmission medium. For example, the units can include a wired interface configured to receive or transmit signals over a wired transmission medium to one or more of the other units. Additionally, the units can include a wireless interface, which may include a receiver, a transmitter or transceiver (such as a radio frequency (RF) transceiver), configured to receive or transmit signals, or both, over a wireless transmission medium to one or more of the other units.

[0051] In some aspects, the CU **210** may host one or more higher layer control functions. Such control functions can include radio resource control (RRC), packet data convergence protocol (PDCP), service data adaptation protocol (SDAP), or the like. Each control function can be implemented with an interface configured to communicate signals with other control functions

hosted by the CU **210**. The CU **210** may be configured to handle user plane functionality (i.e., Central Unit—User Plane (CU-UP)), control plane functionality (i.e., Central Unit—Control Plane (CU-CP)), or a combination thereof. In some implementations, the CU **210** can be logically split into one or more CU-UP units and one or more CU-CP units. The CU-UP unit can communicate bidirectionally with the CU-CP unit via an interface, such as the E1 interface when implemented in an O-RAN configuration. The CU **210** can be implemented to communicate with the DU **230**, as necessary, for network control and signaling.

[0052] The DU **230** may correspond to a logical unit that includes one or more base station functions to control the operation of one or more RUs **240**. In some aspects, the DU **230** may host one or more of a radio link control (RLC) layer, a medium access control (MAC) layer, and one or more high physical (PHY) layers (such as modules for forward error correction (FEC) encoding and decoding, scrambling, modulation and demodulation, or the like) depending, at least in part, on a functional split, such as those defined by the third Generation Partnership Project (3GPP). In some aspects, the DU **230** may further host one or more low PHY layers. Each layer (or module) can be implemented with an interface configured to communicate signals with other layers (and modules) hosted by the DU **230**, or with the control functions hosted by the CU **210**.

[0053] Lower-layer functionality can be implemented by one or more RUs **240**. In some deployments, an RU **240**, controlled by a DU **230**, may correspond to a logical node that hosts RF processing functions, or low-PHY layer functions (such as performing fast Fourier transform (FFT), inverse FFT (iFFT), digital beamforming, physical random access channel (PRACH) extraction and filtering, or the like), or both, based at least in part on the functional split, such as a lower layer functional split. In such an architecture, the RU(s) **240** can be implemented to handle over the air (OTA) communication with one or more UEs **104**. In some implementations, real-time and non-real-time aspects of control and user plane communication with the RU(s) **240** can be controlled by the corresponding DU **230**. In some scenarios, this configuration can enable the DU(s) **230** and the CU **210** to be implemented in a cloud-based RAN architecture, such as a vRAN architecture.

[0054] The SMO Framework **205** may be configured to support RAN deployment and provisioning of non-virtualized and virtualized network elements. For non-virtualized network elements, the SMO Framework **205** may be configured to support the deployment of dedicated physical resources for RAN coverage requirements which may be managed via an operations and maintenance interface (such as an O1 interface). For virtualized network elements, the SMO Framework **205** may be configured to interact with a cloud computing platform (such as an open cloud (O-Cloud) **290**) to perform network element life cycle management (such as to instantiate virtualized network elements) via a cloud computing platform interface (such as an O2 interface). Such virtualized network elements can include, but are not limited to, CUs **210**, DUs **230**, RUs **240** and Near-RT RICs **225**. In some implementations, the SMO Framework **205** can communicate with a hardware aspect of a 4G RAN, such as an open eNB (O-eNB) **211**, via an O1 interface. Additionally, in some implementations, the SMO Framework **205** can communicate directly with one or more RUs **240** via an O1 interface. The SMO Framework **205** also may include a Non-RT RIC **215** configured to support functionality of the SMO Framework **205**.

[0055] The Non-RT RIC **215** may be configured to include a logical function that enables non-real-time control and optimization of RAN elements and resources, Artificial Intelligence/Machine Learning (AI/ML) workflows including model training and updates, or policy-based guidance of applications/features in the Near-RT RIC **225**. The Non-RT RIC **215** may be coupled to or communicate with (such as via an A1 interface) the Near-RT RIC **225**. The Near-RT RIC **225** may be configured to include a logical function that enables near-real-time control and optimization of RAN elements and resources via data collection and actions over an interface (such as via an E2 interface) connecting one or more CUs **210**, one or more DUs **230**, or both, as well as an O-eNB, with the Near-RT RIC **225**.

[0056] In some implementations, to generate AI/ML models to be deployed in the Near-RT RIC **225**, the Non-RT RIC **215** may receive parameters or external enrichment information from external servers. Such information may be utilized by the Near-RT RIC **225** and may be received at the SMO Framework **205** or the Non-RT RIC **215** from non-network data sources or from network functions. In some examples, the Non-RT RIC **215** or the Near-RT RIC **225** may be configured to tune RAN behavior or performance. For example, the Non-RT RIC **215** may monitor long-term trends and patterns for performance and employ AI/ML models to perform corrective actions through the SMO Framework **205** (such as reconfiguration via O1) or via creation of RAN management policies (such as A1 policies).

[0057] Turning now to FIGS. **3-10**, aspects are depicted with reference to one or more components and one or more methods that may perform the actions or operations described herein, where aspects in dashed line may be optional. Although the operations described below in FIGS. **5** and **6** are presented in a particular order and/or as being performed by an example component, it should be understood that the ordering of the actions and the components performing the actions may be varied, depending on the implementation. Moreover, it should be understood that the following actions, functions, and/or described components may be performed by a specially programmed processor, a processor executing specially programmed software or computer-readable media, or by any other combination of a hardware component and/or a software component capable of performing the described actions or functions.

[0058] Referring to FIG. **3**, one example of an implementation of UE **104** may include a variety of components, some of which have already been described above and are described further herein, including components such as one or more processors **312** and one or more memories **316** and one or more transceivers **302** in communication via one or more buses **344**. For example, the one or more processors **312** can include a single processor or multiple processors configured to perform one or more functions described herein. For example, the multiple processors can be configured to perform a certain subset of a set of functions described herein, such that the multiple processors together can perform the set of functions. Similarly, for example, the one or more memories **316** can include a single memory device or multiple memory devices configured to store instructions or parameters for performing one or more functions described herein. For example, the multiple memory devices can be configured to store the instructions or parameters for performing a certain subset of a set of functions described herein, such that the multiple memory devices together can store the instructions or parameters for the set of functions. The one or more processors **312**, one or more memories **316**, and one or more transceivers **302** may operate in conjunction with modem **340** and/or UE communicating component **342** for transmitting UCI indicating whether the UE is transmitting uplink communications based on a received indication of SSB configuration modification, in accordance with aspects described herein.

[0059] In an aspect, the one or more processors **312** can include a modem **340** and/or can be part of the modem **340** that uses one or more modem processors. Thus, the various functions related to UE communicating component **342** may be included in modem **340** and/or processors **312** and, in an aspect, can be executed by a single processor, while in other aspects, different ones of the functions may be executed by a combination of two or more different processors. For example, in an aspect, the one or more processors **312** may include any one or any combination of a modem processor, or a baseband processor, or a digital signal processor, or a transmit processor, or a receiver processor, or a transceiver processor associated with transceiver **302**. In other aspects, some of the features of the one or more processors **312** and/or modem **340** associated with UE communicating component **342** may be performed by transceiver **302**.

[0060] Also, memory/memories **316** may be configured to store data used herein and/or local versions of applications **375** or UE communicating component **342** and/or one or more of its subcomponents being executed by at least one processor **312**. Memory/memories **316** can include any type of computer-readable medium usable by a computer or at least one processor **312**, such as

random access memory (RAM), read only memory (ROM), electronically erasable programmable ROM (EEPROM), tapes, volatile memory, non-volatile memory, optical disk storage, magnetic disk storage, other magnetic storage devices, combinations of the aforementioned types of computer-readable media, or any other medium that can be used to store computer executable code in the form of instructions or data structures that can be accessed by a computer. In an aspect, for example, memory/memories **316** may be a non-transitory computer-readable storage medium that stores one or more computer-executable codes defining UE communicating component **342** and/or one or more of its subcomponents, and/or data associated therewith, when UE **104** is operating at least one processor **312** to execute UE communicating component **342** and/or one or more of its subcomponents.

[0061] Transceiver **302** may include at least one receiver **306** and at least one transmitter **308**. Receiver **306** may include hardware, firmware, and/or software code executable by a processor for receiving data, the code comprising instructions and being stored in a memory (e.g., computer-readable medium). Receiver **306** may be, for example, a radio frequency (RF) receiver. In an aspect, receiver **306** may receive signals transmitted by at least one base station **102**. Additionally, receiver **306** may process such received signals, and also may obtain measurements of the signals, such as, but not limited to, Ec/Io, signal-to-noise ratio (SNR), signal-to-interference-and-noise ratio (SINR), reference signal received power (RSRP), reference signal received quality (RSRQ), received signal strength indicator (RSSI), etc. Transmitter **308** may include hardware, firmware, and/or software code executable by a processor for transmitting data, the code comprising instructions and being stored in a memory (e.g., computer-readable medium). A suitable example of transmitter **308** may including, but is not limited to, an RF transmitter.

[0062] Moreover, in an aspect, UE **104** may include RF front end **388**, which may operate in communication with one or more antennas **365** and transceiver **302** for receiving and transmitting radio transmissions, for example, wireless communications transmitted by at least one base station **102** or wireless transmissions transmitted by UE **104**. RF front end **388** may be connected to one or more antennas **365** and can include one or more low-noise amplifiers (LNAs) **390**, one or more switches **392**, one or more power amplifiers (PAS) **398**, and one or more filters **396** for transmitting and receiving RF signals.

[0063] In an aspect, LNA **390** can amplify a received signal at a desired output level. In an aspect, each LNA **390** may have a specified minimum and maximum gain values. In an aspect, RF front end **388** may use one or more switches **392** to select a particular LNA **390** and its specified gain value based on a desired gain value for a particular application.

[0064] Further, for example, one or more PA(s) **398** may be used by RF front end **388** to amplify a signal for an RF output at a desired output power level. In an aspect, each PA **398** may have specified minimum and maximum gain values. In an aspect, RF front end **388** may use one or more switches **392** to select a particular PA **398** and its specified gain value based on a desired gain value for a particular application.

[0065] Also, for example, one or more filters **396** can be used by RF front end **388** to filter a received signal to obtain an input RF signal. Similarly, in an aspect, for example, a respective filter **396** can be used to filter an output from a respective PA **398** to produce an output signal for transmission. In an aspect, each filter **396** can be connected to a specific LNA **390** and/or PA **398**. In an aspect, RF front end **388** can use one or more switches **392** to select a transmit or receive path using a specified filter **396**, LNA **390**, and/or PA **398**, based on a configuration as specified by transceiver **302** and/or processor **312**.

[0066] As such, transceiver **302** may be configured to transmit and receive wireless signals through one or more antennas **365** via RF front end **388**. In an aspect, transceiver may be tuned to operate at specified frequencies such that UE **104** can communicate with, for example, one or more base stations **102** or one or more cells associated with one or more base stations **102**. In an aspect, for example, modem **340** can configure transceiver **302** to operate at a specified frequency and power

level based on the UE configuration of the UE **104** and the communication protocol used by modem **340**.

[0067] In an aspect, modem **340** can be a multiband-multimode modem, which can process digital data and communicate with transceiver **302** such that the digital data is sent and received using transceiver **302**. In an aspect, modem **340** can be multiband and be configured to support multiple frequency bands for a specific communications protocol. In an aspect, modem **340** can be multimode and be configured to support multiple operating networks and communications protocols. In an aspect, modem **340** can control one or more components of UE **104** (e.g., RF front end **388**, transceiver **302**) to enable transmission and/or reception of signals from the network based on a specified modem configuration. In an aspect, the modem configuration can be based on the mode of the modem and the frequency band in use. In another aspect, the modem configuration can be based on UE configuration information associated with UE **104** as provided by the network during cell selection and/or cell reselection.

[0068] In an aspect, UE communicating component **342** can optionally include a configuration processing component **352** for processing a configuration transmitted by a network entity, such as a SSB configuration configuring SSBs to be transmitted by the network entity, a configured grant configuration configuring resources for uplink transmissions, etc., and/or a UCI component **354** for generating and/or transmitting UCI for the network entity, in accordance with aspects described herein.

[0069] In an aspect, the processor(s) **312** may correspond to one or more of the processors described in connection with the UE in FIG. **10**. Similarly, the memory/memories **316** may correspond to the one or more memories described in connection with the UE in FIG. **10**.

[0070] Referring to FIG. **4**, one example of an implementation of base station **102** (e.g., a base station **102** and/or gNB **180**, as described above) may include a variety of components, some of which have already been described above, but including components such as one or more processors **412** and one or more memories **416** and one or more transceivers **402** in communication via one or more buses **444**. For example, the one or more processors **412** can include a single processor or multiple processors configured to perform one or more functions described herein. For example, the multiple processors can be configured to perform a certain subset of a set of functions described herein, such that the multiple processors together can perform the set of functions. Similarly, for example, the one or more memories **416** can include a single memory device or multiple memory devices configured to store instructions or parameters for performing one or more functions described herein. For example, the multiple memory devices can be configured to store the instructions or parameters for performing a certain subset of a set of functions described herein, such that the multiple memory devices together can store the instructions or parameters for the set of functions. The one or more processors **412**, one or more memories **416**, and one or more transceivers **402** may operate in conjunction with modem **440** and/or BS communicating component **442** for indicating modification of SSB configuration, in accordance with aspects described herein.

[0071] The transceiver **402**, receiver **406**, transmitter **408**, one or more processors **412**, memory/memories **416**, applications **475**, buses **444**, RF front end **488**, LNAs **490**, switches **492**, filters **496**, PAs **498**, and one or more antennas **465** may be the same as or similar to the corresponding components of UE **104**, as described above, but configured or otherwise programmed for base station operations as opposed to UE operations.

[0072] In an aspect, BS communicating component **442** can optionally include a configuring component **452** for generating and/or transmitting one or more configurations for a UE, such as a SSB configuration configuring SSBs to be transmitted by the network entity, a configured grant configuration configuring resources for uplink transmissions, etc., and/or a UCI processing component **454** for receiving and/or processing UCI received for a UE, in accordance with aspects described herein.

[0073] In an aspect, the processor(s) **412** may correspond to one or more of the processors described in connection with the base station in FIG. **10**. Similarly, the memory/memories **416** may correspond to the one or more memories described in connection with the base station in FIG. **10**. [0074] FIG. **5** illustrates a flow chart of an example of a method **500** for transmitting UCI indicating whether a UE is transmitting uplink communications based on a received indication of SSB configuration modification, in accordance with aspects described herein. FIG. **6** illustrates a flow chart of an example of a method **600** for transmitting an indication of modifying a SSB configuration, in accordance with aspects described herein. In an example, a UE **104** can perform the functions described in method **500** shown in FIG. **5** using one or more of the components described in FIGS. **1** and/or **3**. In an example, a node scheduling the UE **104** with communication resources, such as a base station **102** or gNB **180**, a monolithic base station or gNB, a portion of a disaggregated base station or gNB, a UE in sidelink communication, etc., can perform the functions described in method **600** shown in FIG. **6** using one or more of the components described in FIGS. **1** and/or **4**. Methods **500** and **600** are described in conjunction with one another for ease of explanation; however, the methods **500** and **600** are not required to be performed together and indeed can be performed independently using separate devices.

[0075] In method **600**, optionally at Block **602**, a resource grant indicating resources for transmitting uplink communications in a set of time periods can be transmitted for a UE. In an aspect, configuring component **452**, e.g., in conjunction with processor(s) **412**, memory/memories **416**, transceiver **402**, BS communicating component **442**, etc., can transmit, for the UE (e.g., UE **104**), the resource grant indicating resources for transmitting uplink communications in a set of time periods. For example, configuring component **452** can generate the resource grant for the UE **104**, which can be a CG indicating a periodicity in the time domain for the resources, a frequency domain resource allocation, etc. In an example, configuring component **452** can transmit the CG to the UE **104** using semi-static (e.g., radio resource control (RRC)) signaling. In another example, configuring component **452** may activate PUSCH occasions according to the CG using dynamic signaling (e.g., MAC-CE or DCI). In addition, in some examples, configuring component **452** can configure, for the UE (e.g., using semi-static and/or dynamic signaling), a slot configuration indicating slots or symbols within the slots as being for downlink communications, uplink communications, or flexible.

[0076] In method **500**, optionally at Block **502**, a resource grant indicating resources for transmitting uplink communications in a set of time periods can be received from the network entity. In an aspect, configuration processing component **352**, e.g., in conjunction with processor(s) **312**, memory/memories **316**, transceiver **302**, UE communicating component **342**, etc., can receive, from the network entity, the resource grant indicating resources for transmitting uplink communications in the set of time periods. For example, as described, the resource grant can include a CG received in semi-static (e.g., RRC signaling), an activation of CG resources received in dynamic signaling (e.g., MAC-CE or DCI), etc. In any case, for example, configuration processing component **352** can receive the resource grant and determine, based on the resource grant, resources for transmitting uplink communications (e.g., PUCCH or PUSCH). UE communicating component **342** can transmit uplink communications in the resources indicated by the resource grant.

[0077] In method **600**, optionally at Block **604**, a SSB configuration can be transmitted. In an aspect, configuring component **452**, e.g., in conjunction with processor(s) **412**, memory/memories **416**, transceiver **402**, BS communicating component **442**, etc., can transmit the SSB configuration. For example, configuring component **452** can transmit the SSB configuration in broadcast signaling that can be received by multiple UEs, such as SIB 1. In addition, the SSB configuration can indicate time periods (e.g., symbols, slots, or other time divisions) over which the network entity transmits SSBs.

[0078] In method **500**, optionally at Block **504**, a SSB configuration can be received from a

network entity. In an aspect, configuration processing component **352**, e.g., in conjunction with processor(s) **312**, memory/memories **316**, transceiver **302**, UE communicating component **342**, etc., can receive, from the network entity, the SSB configuration. As described, for example, configuration processing component **352** can receive the SSB configuration in SIB 1 or other broadcast signaling. In an example, configuration processing component **352** can process the SSB configuration and determine parameters for receiving SSBs from the network entity, such as time periods over which to receive SSBs. UE communicating component **342** can accordingly receive the SSBs from the network entity in the indicated time periods, in some examples. In addition, in an example, UE communicating component **342** can refrain from transmitting uplink communications in the indicated time periods.

[0079] In method **600**, at Block **606**, an indication to modify the SSB configuration in a first subset of a set of time periods can be transmitted for a UE. In an aspect, configuring component **452**, e.g., in conjunction with processor(s) **412**, memory/memories **416**, transceiver **402**, BS communicating component **442**, etc., can transmit, for the UE (e.g., UE **104**), the indication to modify the SSB configuration in the first subset of the set of time periods. For example, configuring component **452** can transmit the indication to the UE in dynamic signaling (e.g., MAC-CE or DCI) indicating modification of the SSB configuration. In other examples, the indication may be transmitted using semi-static signaling (e.g., RRC), based on occurrence of one or more conditions or detected events, etc. For example, the indication can indicate that an SSB is being added (e.g., an SSB that is not in the original SSB configuration is being transmitted) or that a configured SSB is being removed (e.g., an SSB that is in the original SSB configuration is not being transmitted). In addition, the set of time periods can include time periods (e.g., symbols, slots, or other time divisions) occurring the future.

[0080] In method **500**, at Block **506**, an indication to modify the SSB configuration in a first subset of a set of time periods can be received from a network entity. In an aspect, configuration processing component **352**, e.g., in conjunction with processor(s) **312**, memory/memories **316**, transceiver **302**, UE communicating component **342**, etc., can receive, from the network entity, the indication to modify the SSB configuration in the first subset of the set of time periods. For example, configuration processing component **352** can receive the indication from the network entity in dynamic signaling (e.g., MAC-CE or DCI), as described, which can indicate modification of the originally received SSB configuration (e.g., to add or remove a SSB in at least a portion of a set of time periods). As described above, the UE **104** (e.g., via UCI component) can transmit UCI (e.g., UTO-UCI) including a bitmap of bits to indicate whether PUSCH is transmitted in multiple upcoming valid PUSCH occasions. In an example, UCI component **354** can use the indication to determine which PUSCH occasions are valid (and thus the corresponding bitmap values), and/or whether to transmit PUSCH in a valid PUSCH occasion that may become invalid (based on the modified SSB configuration), etc.

[0081] In method **500**, at Block **508**, UCI indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods can be transmitted for the network entity and based on the indication. In an aspect, UCI component **354**, e.g., in conjunction with processor(s) **312**, memory/memories **316**, transceiver **302**, UE communicating component **342**, etc., can transmit, for the network entity and based on the indication, UCI indicating whether the UE **104** is to transmit uplink communications in the second subset of the set of time periods. For example, as described above and further herein, UCI component **354** can determine, based on the indication to modify the SSB configuration, which PUSCH occasions are considered valid in generating the bitmap.

[0082] In method **600**, at Block **608**, UCI indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods can be received for the UE and based on the indication. In an aspect, UCI processing component **454**, e.g., in conjunction with processor(s) **412**, memory/memories **416**, transceiver **402**, BS communicating component **442**, etc.,

can receive, for the UE and based on the indication, the UCI indicating whether the UE is to transmit uplink communications in the second subset of the set of time periods. For example, UCI processing component **454** can receive the UCI from the UE **104**, and can process the UCI to determine over which PUSCH occasions the UE **104** is planning to transmit uplink communications. In an example, UCI processing component **454** can use similar logic as UCI component **354**, as described above and further herein, to determine which PUSCH occasions are valid or invalid, for determining to which PUSCH occasions the bits in the bitmap correspond. [0083] In method **500**, optionally at Block **510**, the uplink communications can be transmitted, for the network entity, in at least a portion of the second subset of the set of time periods according to the UCI. In an aspect, UE communicating component **342**, e.g., in conjunction with processor(s) **312**, memory/memories **316**, transceiver **302**, etc., can transmit, for the network entity, the uplink communications in at least the portion of the second subset of the set of time periods according to the UCI. Thus, for example, UE communicating component **342** can transmit uplink communications in the valid PUSCH occasions that correspond to the bitmap (or may not transmit in one or more of the valid PUSCH occasions regardless of the indication in the bitmap in some cases).

[0084] In method **600**, optionally at Block **610**, the uplink communications can be received, for the UE, in at least a portion of the second subset of the set of time periods according to the UCI. In an aspect, BS communicating component **442**, e.g., in conjunction with processor(s) **412**, memory/memories **416**, transceiver **402**, etc., can receive, for the UE, the uplink communications in at least the portion of the second subset of the set of time periods according to the UCI. Thus, for example, BS communicating component **442** can receive uplink communications in the valid PUSCH occasions that correspond to the bitmap in the UCI (or may not receive in one or more of the valid PUSCH occasions regardless of the indication in the bitmap in some cases). As described above and further herein, UE communicating component **342** and BS communicating component **442** can use similar logic to determine over which PUSCH occasions to transmit or receive uplink communications.

[0085] In one example, where configuration processing component **352** receives the indication to modify the SSB configuration before (or at least a threshold period of time before) sending the UTO-UCI, UCI component **354** can consider the valid/invalid PUSCH occasions based on the SSB configuration before the indication is received (e.g., regardless of the modifications indicated by the indication). In an example, the threshold period of time can be a processing time threshold related to a time the UE **104** needs to process the received configuration. For example, the threshold period of time can be $T_{sub.proc,2}$, as defined in 5G NR. In this example, if the indication indicates removal of an SSB from the current SSB configuration (and thus a previously invalid PUSCH becomes valid), which is referred to as “Case 1” in the example shown in FIG. 7, UCI component **354** can still consider this PUSCH occasion as invalid in generating the bitmap for indicating resources used for uplink transmissions. In addition, in this example, if the indication indicates addition of an SSB to the current SSB configuration (and thus a previously valid PUSCH becomes invalid), which is referred to as “Case 2” in the example shown in FIG. 7, UCI component **354** may still consider this PUSCH occasion as valid in generating the bitmap, but UE communicating component **342** may refrain from transmitting uplink communications in this PUSCH occasion.

[0086] FIG. 7 illustrates examples of timelines **700** and **702** where the indication to modify a SSB configuration is received before transmitting UCI indicating whether the UE is transmitting uplink communications, in accordance with aspects described herein. Timeline **700** illustrates an example of Case 1, described above, where the indication of modifying the SSB configuration (indication of dynamic SSB adaptation) is received at **704** before transmitting UCI **710**. UCI **710** can include UTO-UCI, as described, which can include a bitmap indicating whether uplink communications are transmitted in valid PUSCH occasions **714** and **718**. PUSCH occasion **716** may be invalid

according to the SSB configuration before modification, but may be indicated in the indication to modify the SSB configuration to remove the SSB (and thus previously configured SSB **720** is not transmitted). In this example, as described above, UCI component **354** can generate the UCI to still consider this PUSCH occasion **716** invalid and not include a bit for this PUSCH occasion **716** (and only include bits for PUSCH occasions **714** and **718**). In addition, in this example, UE communicating component **342** can refrain from transmitting uplink communications in this PUSCH occasion **716**. In an example, UCI processing component **454** can similarly process the UCI considering this PUSCH occasion **716** as invalid (and thus skip this PUSCH occasion **716** in mapping the bits of the bitmap to PUSCH occasions **714** and **718**). In addition, for example, BS communicating component **442** can similarly refrain from receiving uplink communications in this PUSCH occasion **716**.

[0087] Timeline **702** illustrates an example of Case 2, described above, where the indication of modifying the SSB configuration (indication of dynamic SSB adaptation) is received at **704** before transmitting UCI **722**. UCI **722** can include UTO-UCI, as described, which can include a bitmap indicating whether uplink communications are transmitted in valid PUSCH occasions **726**, **728**, and **730**. PUSCH occasion **728** may be valid according to the SSB configuration before modification, but may be indicated in the indication to modify the SSB configuration to add an SSB **732**, rendering this PUSCH occasion **728** invalid. In this example, as described above, UCI component **354** can generate the UCI to still consider this PUSCH occasion **728** valid and can include a bit for this PUSCH occasion **728** as well, but UE communicating component **342** can refrain from transmitting uplink communications in this PUSCH occasion **728**. In an example, UCI processing component **454** can similarly process the UCI considering this PUSCH occasion **728** as valid in mapping the bits of the bitmap to PUSCH occasions **726**, **728**, and **730**. In addition, for example, BS communicating component **442** can also refrain from receiving uplink communications in this PUSCH occasion **728**, regardless of the UTO-UCI bitmap value for this PUSCH occasion **728**, based on the SSB configuration indicating to add a SSB **732** at this PUSCH occasion **728**.

[0088] In another example, where configuration processing component **352** receives the indication to modify the SSB configuration before (or at least a threshold period of time before) sending the UTO-UCI, UCI component **354** can consider the valid/invalid PUSCH occasions based on the SSB configuration after the indication is received (e.g., based on the modifications to the SSB configuration indicated by the indication). In an example, the threshold period of time can be a processing time threshold related to a time the UE **104** needs to process the received configuration. For example, the threshold period of time can be $T_{sub.proc,2}$, as defined in 5G NR. In this example, if the indication indicates removal of an SSB from the current SSB configuration (and thus a previously invalid PUSCH becomes valid), which is referred to as “Case 1” in the example shown in FIG. **8**, UCI component **354** can consider this PUSCH occasion as now valid in generating the bitmap for indicating resources used for uplink transmissions. In addition, in this example, if the indication indicates addition of an SSB to the current SSB configuration (and thus a previously valid PUSCH becomes invalid), which is referred to as “Case 2” in the example shown in FIG. **8**, UCI component **354** may consider this PUSCH occasion as now invalid in generating the bitmap.

[0089] FIG. **8** illustrates examples of timelines **800** and **802** where the indication to modify a SSB configuration is received and considered before transmitting UCI indicating whether the UE is transmitting uplink communications, in accordance with aspects described herein. Timeline **800** illustrates an example of Case 1, described above, where the indication of modifying the SSB configuration (indication of dynamic SSB adaptation) is received at **804** before transmitting UCI **810**. UCI **810** can include UTO-UCI, as described, which can include a bitmap indicating whether uplink communications are transmitted in valid PUSCH occasions **814**, **816**, and **818**. PUSCH occasion **816** may be invalid according to the SSB configuration before modification, but may be

indicated in the indication to modify the SSB configuration to remove the SSB (and thus previously configured SSB **820** is not transmitted). In this example, as described above, UCI component **354** can generate the UCI to consider this PUSCH occasion **816** as valid and can include a bit for this PUSCH occasion **816**. In an example, UCI processing component **454** can similarly process the UCI considering this PUSCH occasion **816** as valid based on the modification of the SSB configuration to remove the previously configured SSB **820**.

[0090] Timeline **802** illustrates an example of Case 2, described above, where the indication of modifying the SSB configuration (indication of dynamic SSB adaptation) is received at **804** before transmitting UCI **822**. UCI **822** can include UTO-UCI, as described, which can include a bitmap indicating whether uplink communications are transmitted in valid PUSCH occasions **826** and **830**. PUSCH occasion **828** may be valid according to the SSB configuration before modification, but may be indicated in the indication to modify the SSB configuration to add an SSB **832**, rendering this PUSCH occasion **828** invalid. In this example, as described above, UCI component **354** can generate the UCI considering this PUSCH occasion **828** as invalid and can not include a bit for this PUSCH occasion **828**. In addition, UE communicating component **342** can refrain from transmitting uplink communications in this now invalid PUSCH occasion **828**. In an example, UCI processing component **454** can similarly process the UCI considering this PUSCH occasion **828** as invalid in mapping the bits of the bitmap to PUSCH occasions **826** and **830** (and not PUSCH occasion **828**) based on the modification of the SSB configuration to add SSB **832** in PUSCH occasion **828**. In addition, for example, BS communicating component **442** can also refrain from receiving uplink communications in this PUSCH occasion **828**.

[0091] In another example, where configuration processing component **352** receives the indication to modify the SSB configuration after (or at least a threshold period of time after) sending the UTO-UCI, UCI component **354** can transmit uplink communications according to the UTO-UCI that it transmitted to the network entity, but can refrain from transmitting over a PUSCH occasion where an SSB is introduced (regardless of the UTO-UCI bit value for that PUSCH occasion). An example is illustrated in FIG. 9.

[0092] FIG. 9 illustrates an example of a timeline **900** where the indication to modify a SSB configuration is received and considered after transmitting UCI indicating whether the UE is transmitting uplink communications, in accordance with aspects described herein. In timeline **900**, the indication of modifying the SSB configuration (indication of dynamic SSB adaptation) is received at **904**, which is after transmitting UCI **910**. UCI **910** can include UTO-UCI, as described, which can include a bitmap indicating whether uplink communications are transmitted in valid PUSCH occasions **914**, **916**, and **918**. PUSCH occasion **916** may be valid according to the SSB configuration before modification, but may be indicated in the indication to modify the SSB configuration to add SSB **920** in PUSCH occasion **916**, rendering PUSCH occasion **916** invalid. As the UTO-UCI is transmitted, however, UE communicating component **342** can follow the indicated bitmap, but can refrain from transmitting uplink communications in PUSCH occasion **916** based on the modified SSB configuration, regardless of the UTO-UCI bit value for PUSCH occasion **916**. In an example, UCI processing component **454** can similarly process the UCI considering this PUSCH occasion **916** as valid (e.g., for the purpose of mapping the other bit to PUSCH occasion **918**), but BS communicating component **442** can refrain from receiving the uplink communications over PUSCH occasion **916** based on the modification of the SSB configuration to add SSB **920**.

[0093] In some examples described herein, the UTO-UCI indication may be applicable only to valid CG PUSCH transmission occasions (TOs). In an example, in 5G NR, (e.g., in technical specification (TS) 38.213), a procedure for a UE reporting UTO-UCI may include the following. If the UE is provided `nrof_UTO_UCI` with value equal to `O.sup.UTO-UCI` in `configuredGrantConfig` of a CG-PUSCH configuration, the UE can multiplex UTO-UCI represented by a bitmap of `O.sup.UTO-UCI` bits in each CG-PUSCH transmission for the CG-PUSCH configuration. The `O.sup.UTO-UCI` bits of UTO-UCI, `õ.sub.0.sup.UTO-UCI`, `õ.sub.1.sup.UTO-UCI`, . . . ,

0.sub.o.sub.UTO-UCA.sub.-1.sup.UTO-UCA, can have a one-to-one mapping to O.sup.UTO-UCI subsequent CG-PUSCH TOs in ascending order of start time. For unpaired spectrum operation, the O.sup.UTO-UCI subsequent CG-PUSCH TOs can exclude invalid ones where a UE does not transmit a PUSCH due to collision of the PUSCH with the DL symbol(s) indicated by tdd-UL-DL-ConfigurationCommon or tdd-UL-DL-ConfigurationDedicated if provided, or a symbol(s) of an SS/PBCH block with index provided by ssb-PositionsInBurst based on the procedures in Clause 11.1 For UE that is indicated to cancel an SSB, the UE may consider the PUSCH occasion as valid and may not exclude the indication from the UTO-UCI if the indication is received T.sub.proc,2 or N2 from the first symbol of the PUSCH. A bit value of '0' can indicate that the UE may transmit CG-PUSCH, and a bit value of '1' can indicate that the UE may not transmit CG-PUSCH, in a corresponding CG-PUSCH TO. When the UE indicates by UTO-UCI a value of '1' for a CG-PUSCH TO, the UE may continue to indicate the value of '1' for the CG-PUSCH TO by UTO-UCI multiplexed in subsequent CG-PUSCH transmissions, and the UE may not transmit CG-PUSCH in the CG-PUSCH TO.

[0094] FIG. 10 is a block diagram of a MIMO communication system 1000 including a base station 102 and a UE 104. The MIMO communication system 1000 may illustrate aspects of the wireless communication access network 100 described with reference to FIG. 1. The base station 102 may be an example of aspects of the base station 102 described with reference to FIG. 1. The base station 102 may be equipped with antennas 1034 and 1035, and the UE 104 may be equipped with antennas 1052 and 1053. In the MIMO communication system 1000, the base station 102 may be able to send data over multiple communication links at the same time. Each communication link may be called a "layer" and the "rank" of the communication link may indicate the number of layers used for communication. For example, in a 2×2 MIMO communication system where base station 102 transmits two "layers," the rank of the communication link between the base station 102 and the UE 104 is two.

[0095] At the base station 102, a transmit (Tx) processor 1020 may receive data from a data source. The transmit processor 1020 may process the data. The transmit processor 1020 may also generate control symbols or reference symbols. A transmit MIMO processor 1030 may perform spatial processing (e.g., precoding) on data symbols, control symbols, or reference symbols, if applicable, and may provide output symbol streams to the transmit modulator/demodulators 1032 and 1033. Each modulator/demodulator 1032 through 1033 may process a respective output symbol stream (e.g., for OFDM, etc.) to obtain an output sample stream. Each modulator/demodulator 1032 through 1033 may further process (e.g., convert to analog, amplify, filter, and upconvert) the output sample stream to obtain a DL signal. In one example, DL signals from modulator/demodulators 1032 and 1033 may be transmitted via the antennas 1034 and 1035, respectively.

[0096] The UE 104 may be an example of aspects of the UEs 104 described with reference to FIGS. 1 and 3. At the UE 104, the UE antennas 1052 and 1053 may receive the DL signals from the base station 102 and may provide the received signals to the modulator/demodulators 1054 and 1055, respectively. Each modulator/demodulator 1054 through 1055 may condition (e.g., filter, amplify, downconvert, and digitize) a respective received signal to obtain input samples. Each modulator/demodulator 1054 through 1055 may further process the input samples (e.g., for OFDM, etc.) to obtain received symbols. A MIMO detector 1056 may obtain received symbols from the modulator/demodulators 1054 and 1055, perform MIMO detection on the received symbols, if applicable, and provide detected symbols. A receive (Rx) processor 1058 may process (e.g., demodulate, deinterleave, and decode) the detected symbols, providing decoded data for the UE 104 to a data output, and provide decoded control information to a processor(s) 1080, or memory/memories 1082.

[0097] The processor(s) 1080 may in some cases execute stored instructions to instantiate a UE communicating component 342 (see e.g., FIGS. 1 and 3).

[0098] On the uplink (UL), at the UE 104, a transmit processor 1064 may receive and process data

from a data source. The transmit processor **1064** may also generate reference symbols for a reference signal. The symbols from the transmit processor **1064** may be precoded by a transmit MIMO processor **1066** if applicable, further processed by the modulator/demodulators **1054** and **1055** (e.g., for single carrier-FDMA, etc.), and be transmitted to the base station **102** in accordance with the communication parameters received from the base station **102**. At the base station **102**, the UL signals from the UE **104** may be received by the antennas **1034** and **1035**, processed by the modulator/demodulators **1032** and **1033**, detected by a MIMO detector **1036** if applicable, and further processed by a receive processor **1038**. The receive processor **1038** may provide decoded data to a data output and to the processor(s) **1040** or memory/memories **1042**.

[0099] The processor(s) **1040** may in some cases execute stored instructions to instantiate a BS communicating component **442** (see e.g., FIGS. **1** and **4**).

[0100] The components of the UE **104** may, individually or collectively, be implemented with one or more ASICs adapted to perform some or all of the applicable functions in hardware. Each of the noted modules may be a means for performing one or more functions related to operation of the MIMO communication system **1000**. Similarly, the components of the base station **102** may, individually or collectively, be implemented with one or more application specific integrated circuits (ASICs) adapted to perform some or all of the applicable functions in hardware. Each of the noted components may be a means for performing one or more functions related to operation of the MIMO communication system **1000**.

[0101] The following aspects are illustrative only and aspects thereof may be combined with aspects of other embodiments or teachings described herein, without limitation.

[0102] Aspect 1 is a method for wireless communication at a UE including receiving, from a network entity, an indication to modify a SSB configuration in a first subset of a set of time periods, and transmitting, for the network entity and based on the indication, UCI indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods.

[0103] In Aspect 2, the method of Aspect 1 includes where the indication is received at least a threshold period of time before the UCI is transmitted, where the indication indicates removing a SSB in the first subset of the set of time periods, and where the second subset of the set of time periods does not include the first subset of the set of time periods.

[0104] In Aspect 3, the method of any of Aspects 1 or 2 includes where the indication is received at least a threshold period of time before the UCI is transmitted, where the indication indicates adding a SSB in the first subset of the set of time periods, and where the second subset of the set of time periods includes the first subset of the set of time periods.

[0105] In Aspect 4, the method of Aspect 3 includes where the UCI indicates the uplink communications are not transmitted in the first subset of the set of time periods.

[0106] In Aspect 5, the method of any of Aspects 1 to 4 includes where the indication is received at least a threshold period of time before the UCI is transmitted, where the indication indicates removing a SSB in the first subset of the set of time periods, and where the second subset of the set of time periods includes the first subset of set of time periods.

[0107] In Aspect 6, the method of Aspect 5 includes where the UCI indicates the uplink communications are transmitted in the first subset of the set of time periods.

[0108] In Aspect 7, the method of any of Aspects 1 to 6 includes where the indication is received at least a threshold period of time before the UCI is transmitted, where the indication indicates adding a SSB in the first subset of the set of time periods, and where the second subset of the set of time periods does not include the first subset of the set of time periods.

[0109] In Aspect 8, the method of any of Aspects 1 to 7 includes where the indication is received after a threshold period of time before the UCI is transmitted or after the UCI is transmitted, where the indication indicates adding a SSB in the first subset of the set of time periods, where the UCI indicates the uplink communications are transmitted in the first subset of the set of time periods, and refraining, based on the indication, from transmitting the uplink communications in the first

subset of the set of time periods.

[0110] In Aspect 9, the method of any of Aspects 1 to 8 includes transmitting, for the network entity, the uplink communications in at least a portion of the second subset of the set of time periods according to the UCI.

[0111] Aspect 10 is a method for wireless communication at a network entity including transmitting, for a UE, an indication to modify a SSB configuration in a first subset of set of time periods, and receiving, for the UE and based on the indication, UCI indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods.

[0112] In Aspect 11, the method of Aspect 10 includes where the indication is transmitted at least a threshold period of time before the UCI is received, where the indication indicates removing a SSB in the first subset of the set of time periods, and where the second subset of the set of time periods does not include the first subset of the set of time periods.

[0113] In Aspect 12, the method of any of Aspects 10 or 11 includes where the indication is transmitted at least a threshold period of time before the UCI is received, where the indication indicates adding a SSB in the first subset of the set of time periods, and where the second subset of the set of time periods includes the first subset of the set of time periods.

[0114] In Aspect 13, the method of Aspect 12 includes where the UCI indicates uplink communications are not transmitted in the first subset of the set of time periods.

[0115] In Aspect 14, the method of any of Aspects 10 to 13 includes where the indication is transmitted at least a threshold period of time before the UCI is received, where the indication indicates removing a SSB in the first subset of the set of time periods, and where the second subset of the set of time periods includes the first subset of set of time periods.

[0116] In Aspect 15, the method of Aspect 14 includes where the UCI indicates uplink communications are transmitted in the first subset of the set of time periods.

[0117] In Aspect 16, the method of any of Aspects 10 to 15 includes where the indication is transmitted at least a threshold period of time before the UCI is received, where the indication indicates adding a SSB in the first subset of the set of time periods, and where the second subset of the set of time periods does not include the first subset of the set of time periods.

[0118] In Aspect 17, the method of any of Aspects 10 to 16 includes where the indication is transmitted after a threshold period of time before the UCI is received or after the UCI is received, where the indication indicates adding a SSB in the first subset of the set of time periods, where the UCI indicates uplink communications are transmitted in the first subset of the set of time periods, and refraining, based on the indication, from receiving the uplink communications in the first subset of the set of time periods.

[0119] In Aspect 18, the method of any of Aspects 10 to 17 includes receiving, for the UE, the uplink communications in at least a portion of the second subset of the set of time periods according to the UCI.

[0120] Aspect 19 is an apparatus for wireless communication including one or more processors, one or more memories coupled with the one or more processors, and instructions stored in the one or more memories and operable, when executed by the one or more processors, to cause the apparatus to perform any of the methods of Aspects 1 to 18.

[0121] Aspect 20 is an apparatus for wireless communication including means for performing any of the methods of Aspects 1 to 18.

[0122] Aspect 21 is one or more computer-readable media including code executable by one or more processors for wireless communications, the code including code for performing any of the methods of Aspects 1 to 18.

[0123] The above detailed description set forth above in connection with the appended drawings describes examples and does not represent the only examples that may be implemented or that are within the scope of the claims. The term “example,” when used in this description, means “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other

examples.” The detailed description includes specific details for the purpose of providing an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, well-known structures and apparatuses are shown in block diagram form in order to avoid obscuring the concepts of the described examples.

[0124] Information and signals may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the above description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, computer-executable code or instructions stored on a computer-readable medium, or any combination thereof.

[0125] The various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed with a specially programmed device, such as but not limited to a processor, a digital signal processor (DSP), an ASIC, a field programmable gate array (FPGA) or other programmable logic device, a discrete gate or transistor logic, a discrete hardware component, or any combination thereof designed to perform the functions described herein. A specially programmed processor may be a microprocessor, but in the alternative, the processor may be any conventional processor, controller, microcontroller, or state machine. A specially programmed processor may also be implemented as a combination of computing devices, e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration.

[0126] The functions described herein may be implemented in hardware, software executed by a processor, firmware, or any combination thereof. If implemented in software executed by a processor, the functions may be stored on or transmitted over as one or more instructions or code on a non-transitory computer-readable medium. Other examples and implementations are within the scope and spirit of the disclosure and appended claims. For example, due to the nature of software, functions described above can be implemented using software executed by a specially programmed processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations. Also, as used herein, including in the claims, “or” as used in a list of items prefaced by “at least one of” indicates a disjunctive list such that, for example, a list of “at least one of A, B, or C” means A or B or C or AB or AC or BC or ABC (i.e., A and B and C).

[0127] Computer-readable media includes both computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A storage medium may be any available medium that can be accessed by a general purpose or special purpose computer. By way of example, and not limitation, computer-readable media can comprise RAM, ROM, EEPROM, CD-ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other medium that can be used to carry or store desired program code means in the form of instructions or data structures and that can be accessed by a general-purpose or special-purpose computer, or a general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of medium. Disk and disc, as used herein, include compact disc (CD), laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers. Combinations of the above are also included within the scope of computer-readable media.

[0128] The previous description of the disclosure is provided to enable a person skilled in the art to make or use the disclosure. Various modifications to the disclosure will be readily apparent to those

skilled in the art, and the common principles defined herein may be applied to other variations without departing from the spirit or scope of the disclosure. Furthermore, although elements of the described aspects and/or embodiments may be described or claimed in the singular, the plural is contemplated unless limitation to the singular is explicitly stated. Additionally, all or a portion of any aspect and/or embodiment may be utilized with all or a portion of any other aspect and/or embodiment, unless stated otherwise. Thus, the disclosure is not to be limited to the examples and designs described herein but is to be accorded the widest scope consistent with the principles and novel features disclosed herein.

Claims

1. An apparatus for wireless communication, comprising: a transceiver; one or more memories configured to, individually or in combination, store instructions; and one or more processors communicatively coupled with the one or more memories, wherein the one or more processors are, individually or in combination, configured to execute the instructions to cause the apparatus to: receive, from a network entity, an indication to modify a synchronization signal block (SSB) configuration in a first subset of a set of time periods; and transmit, for the network entity and based on the indication, uplink control information (UCI) indicating whether the apparatus is to transmit uplink communications in a second subset of the set of time periods.
2. The apparatus of claim 1, wherein the indication is received at least a threshold period of time before the UCI is transmitted, wherein the indication indicates removing a SSB in the first subset of the set of time periods, and wherein the second subset of the set of time periods does not include the first subset of the set of time periods.
3. The apparatus of claim 1, wherein the indication is received at least a threshold period of time before the UCI is transmitted, wherein the indication indicates adding a SSB in the first subset of the set of time periods, and wherein the second subset of the set of time periods includes the first subset of the set of time periods.
4. The apparatus of claim 3, wherein the UCI indicates the uplink communications are not transmitted in the first subset of the set of time periods.
5. The apparatus of claim 1, wherein the indication is received at least a threshold period of time before the UCI is transmitted, wherein the indication indicates removing a SSB in the first subset of the set of time periods, and wherein the second subset of the set of time periods includes the first subset of set of time periods.
6. The apparatus of claim 5, wherein the UCI indicates the uplink communications are transmitted in the first subset of the set of time periods.
7. The apparatus of claim 1, wherein the indication is received at least a threshold period of time before the UCI is transmitted, wherein the indication indicates adding a SSB in the first subset of the set of time periods, and wherein the second subset of the set of time periods does not include the first subset of the set of time periods.
8. The apparatus of claim 1, wherein the indication is received after a threshold period of time before the UCI is transmitted or after the UCI is transmitted, wherein the indication indicates adding a SSB in the first subset of the set of time periods, wherein the UCI indicates the uplink communications are transmitted in the first subset of the set of time periods, and further comprising wherein the one or more processors are, individually or in combination, configured to execute the instructions to cause the apparatus to refrain, based on the indication, from transmitting the uplink communications in the first subset of the set of time periods.
9. The apparatus of claim 1, wherein the one or more processors are, individually or in combination, configured to execute the instructions to cause the apparatus to transmit, for the network entity, the uplink communications in at least a portion of the second subset of the set of time periods according to the UCI.

- 10.** An apparatus for wireless communication, comprising: a transceiver; one or more memories configured to, individually or in combination, store instructions; and one or more processors communicatively coupled with the one or more memories, wherein the one or more processors are, individually or in combination, configured to execute the instructions to cause the apparatus to: transmit, for a user equipment (UE), an indication to modify a synchronization signal block (SSB) configuration in a first subset of set of time periods; and receive, for the UE and based on the indication, uplink control information (UCI) indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods.
- 11.** The apparatus of claim 10, wherein the indication is transmitted at least a threshold period of time before the UCI is received, wherein the indication indicates removing a SSB in the first subset of the set of time periods, and wherein the second subset of the set of time periods does not include the first subset of the set of time periods.
- 12.** The apparatus of claim 10, wherein the indication is transmitted at least a threshold period of time before the UCI is received, wherein the indication indicates adding a SSB in the first subset of the set of time periods, and wherein the second subset of the set of time periods includes the first subset of the set of time periods.
- 13.** The apparatus of claim 12, wherein the UCI indicates uplink communications are not transmitted in the first subset of the set of time periods.
- 14.** The apparatus of claim 10, wherein the indication is transmitted at least a threshold period of time before the UCI is received, wherein the indication indicates removing a SSB in the first subset of the set of time periods, and wherein the second subset of the set of time periods includes the first subset of set of time periods.
- 15.** The apparatus of claim 14, wherein the UCI indicates uplink communications are transmitted in the first subset of the set of time periods.
- 16.** The apparatus of claim 10, wherein the indication is transmitted at least a threshold period of time before the UCI is received, wherein the indication indicates adding a SSB in the first subset of the set of time periods, and wherein the second subset of the set of time periods does not include the first subset of the set of time periods.
- 17.** The apparatus of claim 10, wherein the indication is transmitted after a threshold period of time before the UCI is received or after the UCI is received, wherein the indication indicates adding a SSB in the first subset of the set of time periods, wherein the UCI indicates uplink communications are transmitted in the first subset of the set of time periods, and wherein the one or more processors are, individually or in combination, configured to execute the instructions to cause the apparatus to refrain, based on the indication, from receiving the uplink communications in the first subset of the set of time periods.
- 18.** The apparatus of claim 10, wherein the one or more processors are, individually or in combination, configured to execute the instructions to cause the apparatus to receive, for the UE, the uplink communications in at least a portion of the second subset of the set of time periods according to the UCI.
- 19.** A method for wireless communication at a user equipment (UE), comprising: receiving, from a network entity, an indication to modify a synchronization signal block (SSB) configuration in a first subset of a set of time periods; and transmitting, for the network entity and based on the indication, uplink control information (UCI) indicating whether the UE is to transmit uplink communications in a second subset of the set of time periods.
- 20.** The method of claim 19, wherein the indication is received at least a threshold period of time before the UCI is transmitted, wherein the indication indicates removing a SSB in the first subset of the set of time periods, and wherein the second subset of the set of time periods does not include the first subset of the set of time periods.
-