

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12405558
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Wakatsu; Kohei et al.

Fixing device provided with heater and image forming apparatus

Abstract

A fixing device includes a heater provided with a first heat generator on a substrate and a second heat generator of which a length in a longitudinal direction is shorter than that of the first heat generator, a temperature detector of the heater, a switch for switching a power supply path from an AC power source to the first heat generator or the second heat generator. A controller for controlling the switch to supply power to the first heat generator or the second heat generator. The controller executes a first control in which the switch supplies the power to the first heat generator, and switches a second control in which the switch supplies the power alternately to the first heat generator or the second heat generator when the detected temperature reaches a threshold temperature.

Inventors:	Wakatsu; Kohei (Kanagawa, JP), Yoshida; Tsuguhiro (Kanagawa, JP)
Applicant:	CANON KABUSHIKI KAISHA (Tokyo, JP)
Family ID:	85286821
Assignee:	Canon Kabushiki Kaisha (Tokyo, JP)
Appl. No.:	18/653877
Filed:	May 02, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240288807 A1	Aug. 29, 2024

Foreign Application Priority Data

JP	2021-135856	Aug. 23, 2021
----	-------------	---------------

Related U.S. Application Data

division parent-doc US 17884480 20220809 US 12001157 child-doc US 18653877

Publication Classification

Int. Cl.: G03G15/20 (20060101)

U.S. Cl.:

Field of Classification Search

CPC: G03G (15/2039)

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5465141	12/1994	Asano et al.	N/A	N/A
6178299	12/2000	Kim	N/A	G03G 21/00
2010/0158555	12/2009	Ota	N/A	N/A
2012/0230742	12/2011	Nakagawa et al.	N/A	G03G 15/20
2012/0243894	12/2011	Umeda et al.	N/A	G03G 15/20
2015/0331371	12/2014	Nakajima	N/A	G03G 15/20
2016/0033908	12/2015	Tsunashima et al.	N/A	G03G 15/20
2016/0327894	12/2015	Tsunashima et al.	N/A	G03G 15/20
2016/0342117	12/2015	Minamishima et al.	N/A	G03G 15/20
2017/0060052	12/2016	Narahara et al.	N/A	G03G 15/20
2017/0192378	12/2016	Hashiguchi et al.	N/A	G03G 15/20
2017/0315485	12/2016	Tsunashima et al.	N/A	G03G 15/20
2017/0343929	12/2016	Narahara et al.	N/A	G03G 15/20
2018/0074444	12/2017	Wakatsu et al.	N/A	G03G 15/20
2018/0074445	12/2017	Nishida et al.	N/A	G03G 15/20
2018/0173140	12/2017	Imaizumi et al.	N/A	G03G 15/20
2018/0181039	12/2017	An et al.	N/A	G03G 15/20
2018/0348678	12/2017	Nakamoto et al.	N/A	G03G 15/20
2018/0373189	12/2017	Wakatsu et al.	N/A	G03G 15/20
2019/0171145	12/2018	Imaizumi et al.	N/A	G03G 15/20
2020/0192253	12/2019	Morihara et al.	N/A	N/A
2020/0233346	12/2019	Sato et al.	N/A	G03G 15/20
2020/0233348	12/2019	Nakajima et al.	N/A	G03G 15/20
2020/0233349	12/2019	Takano	N/A	G03G 15/2042
2020/0233350	12/2019	Oi et al.	N/A	G03G 15/20
2020/0233352	12/2019	Doda et al.	N/A	G03G 15/20
2020/0249600	12/2019	Yoshida et al.	N/A	G03G 15/2039
2020/0292981	12/2019	Nagashima	N/A	N/A
2020/0301330	12/2019	Yoshida et al.	N/A	G03G 15/20
2020/0371459	12/2019	Takeda et al.	N/A	G03G 15/20
2021/0063923	12/2020	Odate et al.	N/A	G03G 15/20
2021/0072680	12/2020	Yoshida et al.	N/A	G03G 15/2039
2021/0072681	12/2020	Wakatsu et al.	N/A	G03G 15/2039
2021/0072683	12/2020	Yoshida et al.	N/A	N/A
2021/0072684	12/2020	Doda et al.	N/A	G03G 15/20
2021/0132528	12/2020	Sato et al.	N/A	G03G 15/20
2021/0165351	12/2020	Doda et al.	N/A	G03G 15/20
2021/0232072	12/2020	Nakajima et al.	N/A	G03G 15/20
2021/0278793	12/2020	Maeda et al.	N/A	G03G 15/00
2021/0278794	12/2020	Nakajima	N/A	G03G 15/00
2021/0333732	12/2020	Yoshida et al.	N/A	G03G 15/2039
2021/0333733	12/2020	Doda et al.	N/A	G03G 15/20
2022/0057736	12/2021	Doda et al.	N/A	G03G 15/20
2022/0100128	12/2021	Nakamoto et al.	N/A	G03G 15/20
2022/0253006	12/2021	Doda et al.	N/A	G03G 15/20

2022/0299912	12/2021	Yoshida et al.	N/A	G03G 15/20
2022/0299914	12/2021	Doda	N/A	G03G 15/20
2022/0308509	12/2021	Wakatsu et al.	N/A	G03G 15/20
2022/0365475	12/2021	Nakajima et al.	N/A	G03G 15/00
2023/0064449	12/2022	Nakamoto et al.	N/A	G03G 15/20
2023/0067803	12/2022	Yoshida et al.	N/A	G03G 15/20

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
H04322286	12/1991	JP	N/A
2001-100558	12/2000	JP	N/A
2008250061	12/2007	JP	N/A
2017021287	12/2016	JP	N/A
202098286	12/2019	JP	N/A
2020115184	12/2019	JP	N/A
2020115185	12/2019	JP	N/A
2020115186	12/2019	JP	N/A
2020-126205	12/2019	JP	N/A
2020129021	12/2019	JP	N/A
2020148827	12/2019	JP	N/A
2021006879	12/2020	JP	N/A
2021-043246	12/2020	JP	N/A
2021-043248	12/2020	JP	N/A
2021043245	12/2020	JP	N/A
20200090129	12/2019	KR	N/A

OTHER PUBLICATIONS

Japanese Patent Office dated Mar. 25, 2025 in counterpart Japanese Patent Appln. No. 2021-135856. cited by applicant

Primary Examiner: Bloss; Stephanie E

Assistant Examiner: Harrison; Michael A

Attorney, Agent or Firm: Venable LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a divisional of U.S. application Ser. No. 17/884,480 filed Aug. 9, 2022, currently pending; and claims priority under 35 U.S.C. § 119 to Japan Application JP 2021-135856 filed in Japan on Aug. 23, 2021; and the contents of all of which are incorporated herein by reference as if set forth here in full.

FIELD OF THE INVENTION AND RELATED ART

(1) The present invention relates to a fixing device and an image forming apparatus which is provided with the fixing device.

(2) In the fixing device of the image forming apparatus which performs image forming on a recording material, the toner image is fixed onto the recording material as the recording material passes through a fixing nip portion which is formed by abutting a fixing film which heats a toner image on the recording material with a pressing roller which presses the toner image. When the recording materials, which are narrower than a width of the heater (heating device) which heats the fixing film with respect to a longitudinal direction, are continuously printed, a phenomenon of paper non-passage portion temperature rise, in which temperature gradually rises in an area (non-passage portion) of the fixing nip portion in which the recording material does not pass through, occurs. And when temperature in the non-passage portion rises significantly, fixing members of the fixing device such as the fixing film and the pressing roller, may be damaged by the rise in temperature. Therefore, for example, in Japanese Laid-Open Patent Application (JP-A) 2001-100558, a constitution, in which paper non-

passage portion temperature rise is reduced in the fixing device by switching a plurality of heating members with different lengths of heaters with respect to a longitudinal direction, is proposed.

(3) In a method which is described above, when temperature reaches a predetermined temperature in a center portion of heaters of the fixing device with respect to the longitudinal direction, a control which switches a plurality of heating members is performed. However, depending on a state of the fixing device, after that, it may take time for temperature at end portions of the heaters with respect to a longitudinal direction to rise to temperature which is suitable for image forming, or on the contrary, paper non-passage portion temperature rise may occur, therefore temperature control of the heaters is required according to the state.

SUMMARY OF THE INVENTION

(4) According to an aspect of the present invention, there is provided a fixing device for fixing an unfixed toner image on a recording material to the recording material, the fixing device comprising, a first rotatable member, a heater provided with a first heat generating member on a substrate and a second heat generating member of which a length in a longitudinal direction is shorter than a length of the first heat generating member; and constituted to heat the first rotatable member, a first temperature detecting unit constituted to detect a temperature of the heater, a second rotatable member constituted to form a nip portion with the first rotatable member, a switching unit constituted to switch a power supply path from an AC power source to the first heat generating member or the second heat generating member, a control unit constituted to control the switching unit to supply power to the first heat generating member or the second heat generating member, wherein the control unit executes a first control in which the switching unit supplies the power to the first heat generating member, and switches a second control in which the switching unit supplies the power alternately to the first heat generating member or the second heat generating member when the temperature detected by the first temperature detecting unit reaches a threshold temperature.

(5) Further features of the present invention will become apparent from the following description of exemplary embodiments with reference to the attached drawings.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a view showing an overall constitution of an image forming apparatus in from first through fourth embodiments.

(2) FIG. 2 is a block diagram showing a constitution of a control portion of the image forming apparatus in the first embodiment and the second embodiment.

(3) FIG. 3 is a schematic sectional view illustrating a constitution of a fixing device in from the first through the fourth embodiments.

(4) FIG. 4 is a schematic diagram showing a constitution of heaters in from the first through the fourth embodiments.

(5) FIG. 5 is a schematic diagram showing a sectional view of the heaters in from the first through the fourth embodiments.

(6) FIG. 6 is a schematic diagram showing a constitution of a power control circuit of a fixing device in the first embodiment and the second embodiment.

(7) FIG. 7 is a flowchart showing a control sequence of power supply to heating members in the first embodiment.

(8) FIG. 8 is a diagram illustrating timing of start of switching of the heating members in the first embodiment.

(9) FIG. 9 is a diagram illustrating the timing of start of switching of the heating members in the first embodiment.

(10) FIG. 10 is a flowchart showing the control sequence of the power supply to heating members in the second embodiment 2.

(11) FIG. 11 is a diagram illustrating the timing of start of switching of the heating members in the second embodiment.

(12) FIG. 12 is a block diagram showing a constitution of the control portion of the image forming apparatus in the third embodiment and the fourth embodiment.

(13) FIG. 13 is a schematic diagram showing a constitution of the power control circuit of the fixing device in the third embodiment and the fourth embodiment.

(14) FIG. 14 is a flowchart showing a voltage calculation sequence in the third embodiment and the fourth embodiment.

(15) FIG. 15 is a flowchart showing the control sequence of the power supply to the heating members in the

fourth embodiment.

DESCRIPTION OF THE EMBODIMENTS

(16) In the following, embodiments of the present invention will be specifically described with reference to figures. In the following embodiments, passing a recording material through a fixing nip portion of the fixing device is referred to as passing through. Further, an area in which the recording material is not passed through in the fixing nip portion which corresponds to an area in which heating members heat is referred to as a non-passage area (or a non-passage portion), and an area in which the recording material is passed through is referred to as a passage area (or a passage portion). Furthermore, a phenomenon in which temperature of the non-passage area of the fixing nip portion becomes higher than that of the passage area is referred to as paper non-passage portion temperature rise.

First Embodiment

(17) [Constitution of Image Forming Apparatus]

(18) FIG. 1 is a sectional view showing a constitution of an in-line type color image forming apparatus, which is an image forming apparatus in which the fixing device is mounted according to the first embodiment. A constitution of the electrophotographic color image forming apparatus will be described by using FIG. 1. Incidentally, a first station is a station for image forming of yellow (Y) toner, and a second station is a station for image forming of magenta (M) toner. Further, a third station is a station for image forming of cyan (C) toner, and a fourth station is a station for image forming of black (K) toner.

(19) In the first station, a photosensitive drum **1a** which is an image bearing member is an OPC photosensitive drum. The photosensitive drum **1a** includes multiple layers of functional organic materials, which are constituted of a carrier generating layer which generates an electric charge on metal cylinder by being exposed to light, a charge transporting layer which transports the generated charge, etc., and an electrical conductivity of an outermost layer of the photosensitive drum **1a** is low and the outermost layer of the photosensitive drum **1a** is substantially insulated. A charging roller **2a**, which is a charging unit, is abutted with the photosensitive drum **1a**, and as the photosensitive drum **1a** rotates, the charging roller **2a** is rotationally driven and uniformly charges a surface of the photosensitive drum **1a**. A superimposed voltage of DC voltage or AC voltage is applied to the charging roller **2a**, and discharge is generated in a tiny air gap in an upstream side and a downstream side with respect to a rotational direction of the photosensitive drum **1a** from the nip portion between the charging roller **2a** and the surface of the photosensitive drum **1a**. In this way, the photosensitive drum **1a** is electrically charged. A cleaning unit **3a** cleans toner which is remained on the photosensitive drum **1a** after a primary transfer which will be described below. A developing unit **8a** which is a developing unit accommodates non-magnetic single-component toner **5a**, and includes a developing roller **4a** and a developer applying blade **7a**. The photosensitive drum **1a**, the charging roller **2a**, the cleaning unit **3a** and the developing unit **8a** are accommodated in an integrated process cartridge **9a** (image forming portion) which is dismountable from the image forming apparatus.

(20) An exposure device **11a** which is an exposure unit is constituted of a scanner unit or an LED (light emitting diode) array which reflects laser light by a rotatable polygon mirror and scans on photosensitive drum **1a**, and emits scanning beam **12a**, which is modulated according to an image signal, onto the photosensitive drum **1a**. Further, the charging roller **2a** is connected to a charging high-voltage power source **20a** which is a voltage supply unit to the charging roller **2a**. The developing roller **4a** is connected to a developing high-voltage power source **21a**, which is a voltage supply unit to the developing roller **4a**. A primary transfer roller **10a** is connected to a primary transfer high-voltage power source **22a** which is a voltage supply unit to the primary transfer roller **10a**. A constitution of the first station is as described above, and the second station, the third station and the fourth station include similar constitutions. As for the second station, the third station and the fourth station, same reference numeral is attached to a part which includes a same function as the first station, and b, c and d are attached as a subscript of the reference numeral for each station. Incidentally, in a description below, the subscripts a, b, c and d are omitted except in a case of describing a specific station.

(21) An intermediary transfer belt **13** is supported by three rollers of a secondary transfer opposing roller **15**, a tension roller **14** and an auxiliary roller **19** as stretching member of the intermediary transfer belt **13**. A force in a direction in which the intermediary transfer belt **13** is stretched by a spring (not shown) is applied to only the tension roller **14**, so that an appropriate tension force to the intermediary transfer belt **13** is maintained. The secondary transfer opposing roller **15** rotates by receiving rotational drive from a main motor **99** (see FIG. 2), and the intermediary transfer belt **13**, which is wound around an outer periphery, rotates. The intermediary transfer belt **13** moves at substantially same speed in a direction of an arrow (for example, in a clockwise direction in FIG. 1), with respect to the photosensitive drums from **1a** through **1d** (for example, rotating in a counterclockwise direction in FIG. 1). Further, the primary transfer roller **10** is arranged at a position opposing

the photosensitive drum **1** via the intermediary transfer belt **13** and is rotationally driven as a movement of the intermediary transfer belt **13**. A position in which the photosensitive drum **1** is abutted with the primary transfer roller **10** via the intermediary transfer belt **13** is referred to as a primary transfer position. The auxiliary roller **19**, the tension roller **14** and the secondary transfer opposing roller **15** are electrically grounded. Incidentally, since constitutions of primary transfer rollers from **10b** through **10d** of from the second through the fourth stations are similar to the first transfer roller **10a** of the first station, so descriptions are omitted.

(22) [Image Forming Operation]

(23) Next, an image forming operation of the image forming apparatus which is shown in FIG. **1** will be described. When the image forming apparatus receives a print command during a standby state, it starts the image forming operation. The photosensitive drum **1**, the intermediary transfer belt **13**, etc. start to rotate at a predetermined process speed in the direction of the arrow in the figure by the main motor **99** (see FIG. **2**). The photosensitive drum **1a** is uniformly charged by the charging roller **2a** to which voltage is applied by the charging high-voltage power source **20a**, and then an electrostatic latent image based on image information is formed by the scanning beam **12a** which is emitted from the exposure device **11a**. Toner **5a** in the developing unit **8a** is negatively charged by the developer applying blade **7a** and applied to the developing roller **4a**. And a predetermined developing voltage is applied to the developing roller **4a** by the developing high-voltage power source **21a**. When the electrostatic latent image which is formed on the photosensitive drum **1a** by rotating the photosensitive drum **1a** reaches the developing roller **4a**, the electrostatic latent image is visualized by adhering negative polarity toner, and a toner image of a first color (for example, Y (yellow)) is formed on the photosensitive drum **1a**. Each station (process cartridges from **9b** through **9d**) of other colors of M (magenta), C (cyan) and K (black) (process cartridges **9b** through **9d**) also operates in a similar way. While delaying a writing signal from a controller (not shown) at a timing corresponding to an interval between primary transfer positions of each color, the electrostatic latent image is formed on each of the photosensitive drums from **1a** through **1d** by the scanning beam **12** from the exposure device **11**. DC high voltage of opposite polarity to the toner is applied to each of the primary transfer rollers from **10a** through **10d**. In this way, the toner images on the photosensitive drums from **1a** through **1d** are transferred to the intermediary transfer belt **13** sequentially (hereinafter referred to as a primary transfer), and a multiple toner image is formed on the intermediary transfer belt **13**.

(24) After that, as the toner image is formed, a paper P which is a recording material which is stacked in a cassette **16** (paper feeding portion), is fed by a paper feeding roller **17** which is rotationally driven by a paper feeding solenoid (not shown). The fed paper P is fed to a registration roller **18** (hereinafter referred to as a registration roller) by a feeding roller (not shown). The paper P is synchronized with the toner image on the intermediary transfer belt **13** and is fed to the transfer nip portion which is an abutting portion between the intermediary transfer belt **13** and the secondary transfer roller **25** by the registration roller **18**. A voltage of opposite polarity to the toner is applied to the secondary transfer roller **25** by the secondary transfer high-voltage power source **26**, and multiple toner images of four color which are borne on the intermediary transfer belt **13** are transferred to the paper P (on the recording material) at one time (hereinafter referred to as a secondary transfer). On the other hand, the toner which remains on the intermediary transfer belt **13** after the secondary transfer is completed is cleaned by a cleaning unit **27**. After the secondary transfer is completed, the paper P is fed to the fixing device **50**, and the paper P in which the toner image is fixed is discharged to a discharge tray **30** as a formed image (print, copy). Incidentally, a fixing film **51**, a nip forming member **52**, a pressing roller **53** and a heater **54** of the fixing device **50** will be described below.

(25) [Control Block of the Image Forming Apparatus]

(26) FIG. **2** is a block diagram showing a constitution of a control portion of the image forming apparatus and a printing operation of the image forming apparatus will be described with reference to the diagram. A PC **110** which is a host computer sends a print command which includes image data of print image and printing information to a video controller **91** which is mounted inside the image forming apparatus.

(27) The video controller **91** converts the image data which is received from the PC **110** into exposure data, and forwards it to an exposure control device **93** in an engine controller **92** and also sends the print command to the CPU **94**. The exposure control device **93** is controlled by the CPU **94** and controls the exposure device **11** which turns the laser light on and off according to the exposure data. When the CPU **94**, which is a control unit, receives the print command from the video controller **91**, it starts the image forming operation.

(28) The CPU **94**, a memory **95**, etc. are mounted on the engine controller **92**. The CPU **94** operates according to a program which is stored in the memory **95** in advance. Further, the CPU **94** includes a timer which measures time and the memory **95** stores various information which controls the fixing device **50** which will be described below. The high-voltage power source **96** is constituted of the charging high-voltage power source **20**, the developing high-voltage power source **21**, the primary transfer high-voltage power source **22** and the secondary

transfer high-voltage power source **26**, which are described above. Further, a fixing power control device **97** is constituted of a bidirectional thyristor **56** (hereinafter referred to as a triac) which is a supply control portion, a heating member switching device **57** (see FIG. **6**) as a switching portion which exclusively selects the heating member to which power is supplied, etc. The fixing power control device **97** selects the heating member to which power is supplied in the fixing device **50** and determines an amount of power to be supplied.

(29) A driving device **98** is constituted of the main motor **99**, a fixing motor **100**, etc. Further, a sensor **101** is constituted of a fixing temperature sensor **59** which is a temperature detecting unit which detects temperature of the fixing device **50**, a paper width sensor **31** which detects width of the paper P, etc., and a detection result of the sensor **101** is transmitted to the CPU **94**. The CPU **94** acquires the detection result of the sensor **101**, and controls the exposure device **11**, the high-voltage power source **96**, the fixing power control device **97** and the driving device **98**, based on the detection result. Thus, the CPU **94** forms the electrostatic latent image, transfers the developed toner image onto the paper P and fixes the transferred toner image onto the paper P, etc., and controls an image forming process in which the image data which is received from the PC **110** is printed on the paper P as the toner image. Incidentally, the image forming apparatus to which the present invention is applied is not limited to the image forming apparatus of the constitution which is described in FIG. **1**, however, the image forming apparatus may be an image forming apparatus which is capable of printing the paper P with different width and which is provided with the fixing device **50** which includes the heater **54** as will be described below.

(30) [Constitution of the Fixing Device]

(31) Next, a constitution of the fixing device **50**, which controls a heating device (heater) which heats the toner image on the paper P by the heating member, will be described by using FIG. **3**. Here, "longitudinal direction" refers to a direction of a rotational axis of the pressing roller **53** which is substantially perpendicular to a feeding direction of the paper P which will be described below. Further, a length of the paper P in a direction which is substantially perpendicular to the feeding direction of the paper P (longitudinal direction) refers to width of paper.

(32) FIG. **3** is a schematic sectional view illustrating a constitution of the fixing device **50**. In the fixing device **50**, the paper P which bears the unfixed toner image T is fed from a left side of the figure in a direction of an arrow in the figure, toward the fixing nip portion N which is constituted by abutting the fixing film **51** (hereinafter referred to as a film **51**) with the pressing roller **53**. In the fixing nip portion N, the fixing film **51** is nipped between the fixing roller **53** and the heater **54**. And the paper P is heated while being fed in the fixing nip portion N from the left side in the right direction in the figure, and the toner image T is fixed on the paper P. The fixing device **50** is constituted of the cylindrical film **51**, the nip forming member **52** which holds the film **51**, a pressing roller **53** which forms the fixing nip portion N together with the film **51** and the heater **54** (heater portion) which heats the paper P.

(33) The film **51** is a fixing film as a first rotating member. For example, polyimide is used for a base layer of the film **51**, and an elastic layer which is made of silicone rubber and a release layer which is made of PFA are formed on the base layer. Grease is applied to an inner surface of the film **51** in order to reduce frictional force which is generated between the nip forming member **52**, the heater **54** and the film **51** by rotation of the film **51**.

(34) The nip forming member **52** guides the film **51** from an inside and also forms the fixing nip portion N between the film **51** and the pressing roller **53**. The nip forming member **52** is a member which is rigid, heat-resistant and heat-insulating, and is formed of liquid crystalline polymer, etc. The film **51** is externally fitted onto the nip forming member **52**. The pressing roller **53** is a roller as a second rotating member and is constituted of a core metal **53a**, an elastic layer **53b** and a release layer **53c**. The pressing roller **53** is rotatably held at both end portions with respect to the longitudinal direction and is rotationally driven by the fixing motor **100** (FIG. **2**), and the film **51** is rotated as the pressing roller rotates. The heater **54** which is a heating member is arranged in an inner space of the fixing film **51**, is held by the nip forming member **52** and is in contact with an inner surface of the film **51**. Details of the heater **54** will be described below.

(35) [Overview of the Heater Portion]

(36) Next, the heater **54**, which is a heating portion, will be described. FIG. **4** is a schematic view illustrating a constitution of the heater **54** when the heater **54** in which the heating members are arranged is viewed from a side of the pressing roller **53** which is shown in FIG. **3**. In FIG. **4**, a reference line a is a centerline of the heating members **54b1a**, **54b1b**, **54b2** and **54b3** with respect to the longitudinal direction, and is also a centerline of the paper P which is fed to the fixing nip portion N in the fixing device **50** with respect to the longitudinal direction (direction of width of paper). As shown in FIG. **4**, the heater **54** includes a board **54a**, the heating members **54b1a**, **54b1b**, **54b2** and **54b3**, a conductor **54c**, contact points from **54d1** through **54d4** and a protective glass layer **54e**. The conductor **54c** is a portion which is painted black in the figure. The board **54a** in the embodiment is made of alumina (Al.sub.2O.sub.3) which is ceramic.

(37) Alumina (Al.sub.2O.sub.3), aluminum nitride (AlN), zirconia (ZrO.sub.2), silicon carbide (SiC), etc. are widely known as ceramic board, and among them, alumina (Al.sub.2O.sub.3) is inexpensive and readily available. Further, the board 54a may be made of metal which is excellent in strength. In a case that a metal board is used, stainless steel (SUS) is excellent in price and strength and preferably used. Further, insulating layer may be provided and used for both a ceramic board and a metal board, in case that they are conductive. The heating members 54b1a, 54b1b, 54b2 and 54b3, the conductor 54c and the contact points from 54d1 through 54d4 are arranged on the board 54a (on the board), and in order to ensure insulation between each of the heating members and the film 51, the protective glass layer 54e is coated on top of them.

(38) Length of each heating member in the longitudinal direction (length in a lateral direction in FIG. 4) is different, and a length L1 of the heating members 54b1a and 54b1b in the longitudinal direction is 222 mm, a length L2 of the heating member 54b2 in the longitudinal direction is 188 mm and a length L3 of the heating member 54b3 in the longitudinal direction is 154 mm. A size relationship among the length L1, the length L2 and the length L3 in the longitudinal direction is the length L1>the length L2>the length L3. For example, in a case that the paper P which is used is A4 size, the heating members 54b1a and 54b1b are used. In a case that the paper P which is used is B5 size, the heating member 54b2 is mainly used. In a case that the paper P which is used is A5 size, the heating member 54b3 is mainly used. Further, each heating member is arranged in order of the heating members 54b1a, 54b2, 54b3 and 54b1b in a short direction (in a vertical direction in FIG. 4).

(39) As shown in FIG. 4, the heating members 54b1a (first heating member) and 54b1b (fourth heating member) are electrically connected to a contact point 54d2 (first contact point) on one end side and to a contact point 54d4 (fourth contact point) on the other end side respectively via the conductor 54c. Further, the heating member 54b2 is electrically connected to the contact point 54d2 on one end side and to a contact point 54d3 (third contact point) on the other end side via the conductor 54c. Similarly, the heating member 54b3 is electrically connected to the contact point 54d1 (second contact point) on one end side and to a contact point 54d3 on the other end side via the conductor 54c. Incidentally, as shown in FIG. 4, lengths of the heating members 54b1a and 54b1b in the longitudinal direction are same as the length L1, and the two heating members 54b1a and 54b1b are always used at a same time. Hereafter, a pair of the heating members 54b1a and 54b1b are collectively referred to as the heating member 54b1. Further, a resistance value of the heating member 54b1 is 10.7 ohms (combined resistance of heating members 54b1a and 54b1b), a resistance value of the heating member 54b2 is 24.1 ohms and a resistance value of the heating member 54b3 is 24.1 ohms. When a power source voltage of the AC power source 55 (see FIG. 6) is 120 V, the maximum value of average power of each heating member is as follows: the heating member 54b1 is 1346 W, and the heating member 54b2 and the heating member 54b3 are 598 W.

(40) In FIG. 4, an area which is surrounded by a dashed line is the fixing temperature sensor 59. The dashed line indicates that the fixing temperature sensor 59 is arranged on a back side of the heater board 54a (opposite side of a surface in which the heating members 54b1, 54b2 and 54b3 are arranged) and also indicates a position in which the fixing temperature sensor 59 is abutted with the heater board 54a. A main thermistor 59a which detects temperature of the fixing temperature sensor 59, is arranged on a centerline of the heating members 54b1, 54b2 and 54b3 with respect to the longitudinal direction and on the reference line a which is a centerline of the paper P which is fed to the fixing device 50. In the embodiment, the fixing temperature sensor 59, which is a first temperature detecting unit, is arranged in a center of the heater 54 with respect to the longitudinal direction, however, an arrangement position of the fixing temperature sensor 59 is not limited to this position. Although an effect of the present invention may be obtained when the fixing temperature sensor 59 is arranged within a range of the fixing nip portion N, it is more preferable that the fixing temperature sensor 59 is arranged inside the heating member 54b3 with respect to the longitudinal direction which is a heating member whose length is short with respect to the longitudinal direction.

(41) [Constitution of the Heater Portion]

(42) FIG. 5 shows a schematic diagram showing a section of the heater 54, when the heater 54, which is shown in FIG. 4, is cut at the centerline of the paper P with respect to the longitudinal direction (the reference line a in FIG. 4) which is fed to the fixing device 50. The fixing temperature sensor 59, which is a temperature detecting unit which detects the temperature of the heater 54, includes following members. That is, the fixing temperature sensor 59 is constituted of the thermistor 59a, a holder 59b, a ceramic paper 59c which blocks heat conduction between the holder 59b and the thermistor 59a, and an insulating resin sheet 59d which physically and electrically protects the thermistor 59a. The thermistor 59a is a temperature detecting element whose resistance value changes and whose output voltage changes according to the temperature of the heater 54, and is connected to the CPU 94 by Dumet wire (not shown) and wiring. The CPU 94 controls the temperature of the heater 54, based on a temperature detection result of the fixing temperature sensor 59 (the thermistor 59a). The fixing temperature sensor 59 is arranged on a surface opposite side of a surface of the board 54a in which the heating

members **54b1**, **54b2** and **54b3** which are covered by the protective glass layer **54e** and is in contact with the board **54a**.

(43) [Power Control Circuit]

(44) FIG. **6** is a schematic diagram showing a constitution of a power control circuit of the fixing device **50**. The fixing device **50** in the embodiment forms a desired temperature distribution of the heater **54** with respect to the longitudinal direction by switching the heating members to which power is supplied according to a size of the paper **P**.

(45) The power control circuit of the fixing device **50** includes the triacs **56a** and **56b** which are switching units which connect or disconnect power supply paths, a triac condition detecting portion **58** and a relay **60** (second relay) which blocks the power supply to all of the heating members. The triacs **56a** and **56b** connect or disconnect the power supply path from the AC power source **55** to each of the heating members **54b1**, **54b2** and **54b3**. The heating member switching device **57** is constituted of a changeover contact relay in the embodiment (hereafter referred to as a relay **57**). Further, the triac condition detecting portion **58** monitors ON condition or OFF condition of the triacs **56a** and **56b**.

(46) The triac **56a** (first switch) connects (ON condition) or disconnects (OFF condition) the power supply path between the AC power source **55** and the contact point **54d4** of the heater **54**. On the other hand, the triac **56b** (second switch) connects (ON condition) or disconnects (OFF condition) the power supply path between the AC power source **55** and the contact point **54d3** of the heater **54** via the relay **57**, or between the AC power source **55** and the contact point **54d1** of the heater **54**. The relay **57** (first relay) is capable of switching the contact point **54d3** of the heater **54** to connect the triac **56b** or the AC power source **55**.

(47) For example, in a case of supplying power to the heating member **54b1** from the AC power source **55**, the triac **56a** is turned on to connect the AC power source **55** to the contact point **54d4** of the heater **54**, and turn off the triac **56b**. Thus, the heating members **54b1** (**54b1a**, **54b1b**) are connected to the AC power source **55** via the contact points **54d2** and **54d4** of the heater **54**. Further, in a case of supplying power to the heating member **54b2** from the AC power source **55**, the triac **56b** is turned on to connect the AC power source **55** to the relay **57**, the relay **57** is controlled to connect the contact point **54d3** of the heater **54** to the triac **56b**, and the triac **56a** is turned off. Thus one end of the heating member **54b2** is connected to the AC power source **55** via the contact point **54d3** of the heater **54**, the relay **57** and the triac **56b**, and the other end of the heating member **54b2** is connected to the AC power source **55** via the contact point **54d2** of the heater **54**.

(48) Further, in a case of supplying power to the heating member **54b3** from the AC power source **55**, the triac **56b** is turned on, the relay **57** is controlled to connect the contact point **54d3** of the heater **54** to the AC power source **55**, and the triac **56a** is turned off. Thus one end of the heating member **54b3** is connected to the AC power source **55** via the contact point **54d3** of the heater **54**, the relay **57**, and the other end of the heating member **54b3** is connected to the AC power source **55** via the contact point **54d1** of the heater **54**. Incidentally, an operation of ON and OFF of the triacs **56a** and **56b** is performed by a command (control signal) from the CPU **94**.

(49) The triac condition detecting portion **58** detects the ON condition and the OFF condition of the triacs **56a** and **56b**. In a case that the triacs **56a** and **56b** are turned on simultaneously due to an unexpected failure of the CPU **94**, for example, the triac condition detecting portion **58** forcibly blocks the power supply from the AC power source **55** to the fixing device **50** (heater **54**) by setting the relay **60** to the OFF condition. Thus, a situation, that only one of the triacs **56a** and **56b** is in the ON condition or both of them are in the OFF condition, is secured, and it is possible to prevent failure of the fixing device **50**.

(50) In this way, the triacs **56a** and **56b**, the triac condition detecting portion **58**, and the relay **57** operate as switching portions which switch connections of the power supply paths so that power is supplied to only one of the three heating members **54b1**, **54b2** and **54b3** from the AC power source **55**. In the embodiment, the switching portions with the constitutions are used, however, the switching portions may be capable of supplying power to only one of the heating members and a constitution for controlling the power supply path is not limited to the constitution which is described above.

(51) Further, in the embodiment, a usage ratio of heating members **54b1**, **54b2** and **54b3** (which is also a power supply ratio to the heating members **54b1**, **54b2** and **54b3**) is controlled according to the size of the paper **P** to form a desired temperature distribution of the heater with respect to the longitudinal direction. The CPU **94** calculates an amount of power which is required to set the heater **54** to the desired temperature from temperature information in which the fixing temperature sensor **59** (the thermistor **59a**) detects. In the embodiment, PI control is used, however, a control method is not limited to PI control.

(52) In order to achieve the desired usage ratio of the heating members, the CPU **94** operates the triacs **56a** and **56b** and the heating member switching device **57** and allocates usage time (time ratio of power supply) of each

of the heating members **54b1**, **54b2** and **54b3**. Switching of the heating member is performed every cycle of power frequency of the AC power source **55**. For example, in a case that the usage ratio (power supply ratio) of the heating members **54b1a** and **54b1b** is 2 and the usage ratio (power supply ratio) of the heating member **54b2** is 8, a state that the AC power source **55** is connected to the heating member **54b1** is continued for a period of $1 \text{ cycle} \times 2 = 2 \text{ cycles}$. After that, an operation, of switching the heating members to which power is supplied, continuing a state that the AC power source **55** is connected to the heating member **54b2** for a period of $1 \text{ cycle} \times 8 = 8 \text{ cycles}$, and connecting the AC power source **55** to the heating member **54b1** again, is repeated. In the embodiment, the usage ratio (power supply ratio) is possible to switch from 10:0 to 0:10 in increments of ratio 1.

(53) In the embodiment, as described above, the desired usage ratio of the heating members (power supply ratio) is achieved by allocating the power supply time to the desired heating members, however, a method is not limited to this. An amount of power supplied to each of the heating members may be distributed by time, voltage, electric current, or a combination of two of them. For example, the desired power supply ratio to each of the heating members may be achieved by mounting the triacs on each of the heating members as a heating member control unit, switching the ON/OFF conditions of each of the triacs by the CPU **94** to control an amount of electric current which is supplied to each of the heating members. Further, a resolution (from 10:0 to 0:10) of the usage ratio (power supply ratio) is not limited to this.

(54) [Count Temperature Prediction Method]

(55) Next, a count temperature prediction method which is a temperature prediction unit which predicts temperature of each member of the fixing device **50**, will be described. In the embodiment, the temperature of each member of the fixing device **50** (for example, the film **51**, the pressing roller **53**, the nip forming member **52**, etc.) is predicted by using a count value. The count value is updated by the CPU **94** and is added by +1 for each sheet of the paper P which is fixed in the fixing device **50**. The greater a number of sheets of the paper P which is processed for fixing in the fixing device **50**, the greater the count value becomes. On the other hand, in a standby state after the fixing process is completed, each member of the fixing device **50** cools down naturally, so the count value is also subtracted and decreased with time. Specifically, a cooling characteristics of each member of the fixing device **50** is examined in advance, and the count value is decreased by using a calculation formula in which an elapsed time is variable. In this way, a method of predicting the temperature of each member of the fixing device **50** by managing the count value is referred to as a count temperature predicting method.

(56) A period from the count value of 0 to the first count value is referred to as a zone 1, and a period from the first count value to the second count value is referred to as a zone 2, and the CPU **94** changes a switching frequency of the heating members according to the zone number. The number of zones is not limited to two, however, it may be three or more. In the embodiment, the first count value is 30, the second count value is 100 and the third count value is 200, and the zones are divided into four zones: the zone 1, the zone 2, the zone 3 and the zone 4. When printing is started from a Cold condition (the count value is 0) in which the temperature of the fixing device **50** is room temperature, the first count value reaches 30 at a time of printing 30 sheets. Therefore, the zone 1 ends when a fixing process for the 30th sheet of the paper P is completed, and switches to the zone 2 from the 31st sheet of paper P.

(57) Next, an actual operation during printing in the embodiment will be described. Here, a case of continuous printing of the A5 size paper P will be described. In the embodiment, the fixing device **50** performs fixing operation of the A5 size paper P by switching between the heating member **54b1** whose length (width) with respect to the longitudinal direction is the largest and the heating member **54b3** whose width with respect to the longitudinal direction corresponds to the width of the A5 size paper P. Incidentally, in a case of continuous printing of the B5 size paper P, the fixing device **50** performs fixing operation of the paper P by switching between the heating member **54b1** whose length (width) with respect to the longitudinal direction is the largest and the heating member **54b2** whose width with respect to the longitudinal direction corresponds to the width of the B5 size paper P. Similarly, in a case of continuous printing of the A4 size or the letter size paper P, the fixing device **50** performs fixing operation of the paper P by using only the heating member **54b1** whose length (width) with respect to the longitudinal direction is the largest. In a following, as an example of printing on paper P, the A5 size paper P will be used for printing.

(58) In a case that the zone number which is described above is small, each member of the fixing device **50** is in a low temperature and, in this case, more power is supplied to the heating member **54b1** which is a heating member whose length with respect to the longitudinal direction is the longest. The reason for this is to melt grease which is inside the film **51** uniformly in the fixing nip portion N with respect to the longitudinal direction. When there are some low temperature areas due to temperature unevenness in the film **51** with respect to the longitudinal direction, since the grease does not melt uniformly, a sliding resistance of the film **51** is not uniform

with respect to the longitudinal direction, and, as a result, the film 51 may be deformed.

(59) On the other hand, in a case that the zone number is greater, each member of the fixing device 50 is in a higher temperature and, in this case, power is supplied to the heating member 54b1 at a constant rate and more power is supplied to the heating member 54b3. This prevents the film 51 from deforming due to dropping temperature at end portions of the heating member with respect to the longitudinal direction and uniformity of sliding resistance of the film 51. However, when the temperature at the end portions of the heating member with respect to the longitudinal direction becomes too high, it may exceed heat resistance temperature of the film 51 and damage the film 51. Further, when the temperature at the end portions of the heating member with respect to the longitudinal direction is too low or too high compared to temperature at a center portion, it may cause uneven temperature of the paper P which passes through the fixing nip portion N. As a result, in an area of end portions of the paper P which passes through the fixing nip portion N, excessive or insufficient heat supply to the toner on the paper P may occur and poor image quality may occur. Therefore, in a case of printing the paper P whose paper width is small, it is preferable to keep temperature difference between a paper passage area of the film 51 in which the paper P passes through and a paper non-passage area of the film 51 in which the paper P does not pass through within an appropriate range.

(60) [Usage Ratio of the Heating Members and Amount of Power Supplied in Each Zone]

(61) Table 1 which is shown below is a table showing a usage ratio (power supply ratio) of the heating members 54b1 and 54b3 in each zone when the A5 size paper P is printed and amounts of maximum average power supply in case that the power source voltage is 120V and 110V. The usage ratio indicates a usage ratio of the heating member 54b1 vs. the heating member 54b3. In a case that AC voltage of the AC power source 55 is 120V, the maximum value of the average power of the heating member 54b1 is 1346 W and the maximum value of the average power of the heating member 54b3 is 598 W. Further, in a case that the AC voltage of the AC power source 55 is 110V, the maximum value of the average power of the heating member 54b1 is 1131 W and the maximum value of the average power of the heating member 54b3 is 502 W. In a case of controlling the usage ratio of the heating member as shown in Table 1, the maximum value of the average power also changes according to the usage ratio of heating members. In a case that the power source voltage is 120V and the zone is the zone 4, for example, the maximum value of the average power is $1346 \text{ W (the heating member 54b1)} \times (2/10) + 598 \text{ W (the heating member 54b3)} \times (8/10) = 747.6 \text{ W} \approx 748 \text{ W}$. Similarly, in a case that the power source voltage is 110V and the zone is the zone 3, the maximum value of the average power is $1131 \text{ W (the heating member 54b1)} \times (4/10) + 502 \text{ W (the heating member 54b3)} \times (6/10) = 753.6 \text{ W} \approx 754 \text{ W}$.

(62) TABLE-US-00001 TABLE 1 Zone 1 2 3 4 Usage ratio (heating 10:0 5:5 4:6 2:8 member 54b1:heating member 54b3) Maximum average 1346 972 897 748 power [W] at 120 V of power source voltage Maximum average 1131 816 754 628 power [W] at 110 V of power source voltage

(63) Even when the heater 54 of the fixing device 50 is sufficiently warmed up, in a case that the paper P does not pass through the fixing nip portion N for a long period of time, it is preferable to control the temperature of the heater 54 by using the heating member (the heating member 54b1 in the embodiment) whose width (length) with respect to the longitudinal direction is long. This is because temperature difference between the paper passage area and the paper non-passage area is less likely to increase when the fixing nip portion N is heated uniformly across the width with respect to the longitudinal direction, since the paper P, which takes amount of heat from the heater 54, does not pass through the fixing nip portion N. Further, this is because it is possible to achieve the temperature of the heater 54 to a target temperature more quickly, since larger amount of power supply over an entire width of the fix nip portion N with respect to the longitudinal direction is possible when the heating member whose width (length) with respect to the longitudinal direction is long.

(64) On the other hand, in a case that the paper P does not pass through the fixing nip portion N for a long period of time, temperature may drop in the paper non-passage area of the fixing nip portion N when the power supply is switched between the heating member whose width with respect to the longitudinal direction is long (for example, the heating member 54b1) and the heating member whose width with respect to the longitudinal direction is short (for example, the heating member 54b3). Further, a time for achieving the target temperature of the heater 54 may longer since the amount of the average power which is supplied is decreased by switching control of the heating members. In the embodiment, the temperature of the heater 54 is controlled as described below, during a warmup period before the paper P reaches the fixing nip portion N, or in a case that there is an interval from the paper P passes through the fixing nip portion N to the subsequent paper P reaches the fixing nip portion N. That is, regardless of the zone which is determined based on the count value which is described above, temperature of the heater 54 is controlled by using only the heating member 54b1 which is a heating member whose width with respect to the longitudinal direction is long.

(65) [Control Sequence for Supplying Power to the Heating Members]

(66) FIG. 7 is a flowchart showing a control sequence for performing power supply to the heating members **54b1** and **54b3** when a print job is executed to print the A5 size paper P. A process in FIG. 7 is launched when a print job is started and executed by the CPU **94**. Power supply periods to the heating members **54b1** and **54b3** are determined based on the usage ratio (which is also the power supply ratio) of the heating members **54b1** and **54b3** according to the zones which corresponds to the count values which are shown in Table 1 described above. Incidentally, updating of the count value which determines the zone is performed in a separate process.

(67) When a print job is started, in step (hereinafter referred to as S) **100**, the CPU **94** starts power supply to the heating member **54b1** based on PI control (first control). In detail, the CPU **94** turns on the triac **56a** and turns off the triac **56b**, and power supply is performed from the AC power supply **55** to the heating member **54b1**. In **S101**, the CPU **94** receives temperature information of the heater **54** from the fixing temperature sensor **59** and determine whether the temperature of the heater **54** reaches a threshold temperature which starts switching control (second control) of the heating members. In a case that the CPU **94** determines that the temperature of the heater **54** reaches the threshold temperature, the CPU **94** proceeds with the process to **S102**, and in a case that the CPU **94** determines that the temperature of the heater **54** does not reach the threshold temperature, the CPU **94** returns the process to **S101**.

(68) In **S102**, the CPU **94** determines the zone based on the count value and receive the usage ratio (which is also a power supply period ratio) of the heating members **54b1** and **54b3** in the zone which is determined by Table 1. In **S103**, the CPU **94** starts power supply to the heating member **54b1** based on PI control, and also resets and starts the timer. In **S104**, the CPU **94** refers to the timer and determines whether the power supply period to the heating member **54b1** is passed. In a case that the CPU **94** determines the power supply period to the heating member **54b1** is passed, the CPU **94** proceeds with the process to **S105**, and in a case that the CPU **94** determines the power supply period to the heating member **54b1** is not passed, the CPU **94** returns the process to **S104**.

(69) In **S105**, the CPU **94** starts power supply to the heating member **54b3** based on PI control. In detail, the CPU **94** turns off the triac **56a**, turns on the triac **56b** and switches the heating member switching device **57** so that the contact point **54d3** of the heater **54** is connected to the AC power supply **55**, and then, power supply from the AC power supply **55** to the heating member **54b3** is performed. Furthermore, the CPU **94** resets and starts the timer. In **S106**, the CPU **94** refers to the timer and determines whether the power supply period to the heating member **54b3** is passed. In a case that the CPU **94** determines the power supply period to the heating member **54b3** is passed, the CPU **94** proceeds with the process to **S107**, and in a case that the CPU **94** determines the power supply period to the heating member **54b3** is not passed, the CPU **94** returns the process to **S106**. In **S107**, the CPU **94** determines whether the print job is completed. In a case that the CPU **94** determines that the print job is completed, it terminates the process, and in a case that the CPU **94** determines that the print job is not completed, the CPU **94** returns the process to **S102**.

(70) [Timing of Start of Switching of the Heating Members]

(71) (In a Case that the Power Source Voltage is 120V)

(72) Next, a timing of start of switching of the heating members during paper passage in the embodiment. FIG. 8 is a diagram illustrating a relationship between the heating members in which power supply is performed at the power source voltage of 120V and a detection temperature of the fixing temperature sensor **59** during printing of the A5 size paper P in the zone 4. In FIG. 8, in order from a top, the heating members to which power is supplied (indicated as the heating members to which power is supplied in the figure), and a timing when the A5 size paper P reaches at the fixing nip portion N (indicated as a timing of paper arriving in the figure) are shown. Furthermore, a graph which is shown at a bottom of FIG. 8 shows temperature change of the heater **54** which is detected by the fixing temperature sensor **59** after a start of printing operation of the image forming apparatus. A vertical axis of the graph in FIG. 8 shows the temperature of the heater **54** which is detected by the fixing temperature sensor **59** (indicated as a thermistor detection temperature in the figure) (unit: ° C.), and a horizontal axis shows an elapsed time after a start of printing operation (unit: sec).

(73) The target temperature of the heater **54** in the embodiment is 220° C., as shown in the graph in FIG. 8. Further, the threshold temperature (indicated as a thermistor threshold temperature in the graph) of the heater **54** which starts a switching control of the heating members **54b1** and **54b3** is 210° C. In the following, the threshold temperature of the heater **54** which starts the switching control of the heating member is referred to as a thermistor threshold temperature or the threshold temperature. The threshold temperature is determined experimentally based on temperature rise in the paper non-passage area of the heater **54** and its tracking condition to the target temperature, as will be described below. When the timing to start switching control of the heating member is delayed, the fixing film **51** may be deformed in a case that temperature rise in the paper non-passage area of the fixing nip portion N occurs and the temperature rise in the paper non-passage area of the

fixing nip portion N is significant. Therefore, it is necessary to adjust the timing of switching the heating members to keep the temperature of the heater 54 low enough to allow enough margin for the temperature of the paper non-passage area of the fixing nip portion N in which the fixing film 51 is deformed. Further, when the timing to start switching control of the heating members is early, the timing of tracking to the target temperature of the heater 54 may be delayed due to reduction of the maximum amount of power which is possible to supply to the heating member 54b1. Therefore, it is necessary to adjust the timing of switching the heating members in a range of that the timing for the heater 54 to reach the target temperature is not too late. Further, the warmer the heater 54 of the fixing device 50 is, the easier it is for the paper non-passage area of the fixing nip portion N to rise in temperature, so the timing for tracking to the target temperature is earlier. Therefore, in this case, it is preferable that the thermistor threshold temperature of the heater 54 is low. In the embodiment, the thermistor threshold temperature varies depending on the zone, which is determined based on the count value, and the greater the zone number, the lower the thermistor threshold temperature is set.

(74) In the embodiment, the heater 54 is heated by the heating member 54b1 whose length is long with respect to the longitudinal direction and, after detecting the fixing temperature sensor 59 detects that the temperature of the heater 54 has reached the threshold temperature, a control in which the heating member 54b1 and the heating member 54b3 whose length is short with respect to the longitudinal direction are alternately switched, is performed. First, a warmup operation to heat the fixing device 50 is started at a same time as the printing operation is started. Specifically, as the start of the printing operation, the power supply to the heating member 54b1 and the rotating operation of the pressing roller 53 start. The CPU 94 performs the power supply to the heating member 54b1 so that temperature detected by the fixing temperature sensor 59 quickly approaches the target temperature (first control). As shown in a graph in FIG. 8, four seconds after the start of the power supply, the detected temperature of the fixing temperature sensor 59 reaches the threshold temperature of 210° C., and a control which switches the heating member 54b1 and the heating member 54b3 alternately is started (second control). Incidentally, a leading edge of the A5 size paper P enters the fixing nip portion N 4.5 seconds after the start of the power supply. As described above, in a case of the power source voltage of the AC power source 55 is 120V, the maximum average power when the power supply is performed by using only the heating member 54b1 is 1346 W, and the maximum average power when controlling by switching the heating member 54b1 and the heating member 54b3 in the zone 4 is 748 W. Therefore, the maximum amount of power which is supplied to the heater 54 is reduced when changing from the control which uses only the heating member 54b1 to the switching control which uses the heating member 54b1 and the heating member 54b3. However, in the embodiment, the heater 54 is heated sufficiently, in a condition that the maximum amount of power which is able to supply is large, until the detected temperature of the fixing temperature sensor 59 reaches the threshold temperature, and then the control in which the power supply is performed by switching the heating member 54b1 and the heating member 54b3 starts. Therefore, the temperature of the heater 54 does not decrease even after the maximum amount of power is reduced, the temperature in the center portion of the heater 54 with respect to the longitudinal direction tracks the target temperature, and image defects due to insufficient temperature of the fixing device 50 are not occurred.

(75) (In a Case that the Power Source Voltage is 110 V)

(76) Next, a printing operation in a case that the power source voltage is low will be described by using FIG. 9. FIG. 9 is a diagram illustrating a relationship between the heating member in which the power supply is performed in a case that the power supply is 110V and the detected temperature of the fixing temperature sensor 59 when the A5 size paper P in the zone 4 is printed. FIG. 9 is a diagram which is a similar constitution of FIG. 8, and an explanation of a view of the figure is omitted. Incidentally, the target temperature of the heater 54 is 220° C., which is same as in FIG. 8. Further, the threshold temperature of the heater 54 (described as a thermistor threshold temperature in the graph) which starts the switching control of the heating members 54b1 and 54b3 is 210° C.

(77) In the case that the power source voltage is 110V, as well as in the case that the power source voltage is 120V, first of all, the power supply from the AC power source 55 to the heating member 54b1 and the rotational operation of the pressing roller 53 are started at a same time as a start of printing operation. Compared to FIG. 8 in which the power source voltage is 120V, in a graph in FIG. 9 in the case that the power source voltage is 110V, the detected temperature of the fixing temperature sensor 59 increases slowly. The detected temperature of the heater 54 of the fixing temperature sensor 59 (thermistor detected temperature) is 201° C. at 4.5 seconds from the start of the printing operation when the A5 size paper P enters the fixing nip portion N, and has not reached at 210° C. which is the thermistor threshold temperature. Five seconds after the start of the printing operation, the detected temperature of the heater 54 by the fixing temperature sensor 59 reaches the thermistor threshold temperature of 210° C., and the control of the power supply which switches the heating member 54b1

and the heating member **54b3** is started.

(78) As shown in Table 1, in the case that the power source voltage is 110V, the maximum average power is 1131 W when the control of the power supply is performed by using only the heating member **54b1**. On the other hand, in a case that the control of the power supply is performed by switching the heating member **54b1** and the heating member **54b3** in the zone 4, the maximum average power is 628 W. In a case of being changed from the control which uses only the heating member **54b1** to switching control which uses the heating member **54b1** and the heating member **54b3**, the maximum amount of power which is supplied to the heater **54** is reduced. However, in the embodiment, the heater **54** is heated sufficiently until the detected temperature of the heater **54** by the fixing temperature sensor **59** reaches the threshold temperature, and the control of the power supply is performed to switch between the heating member **54b1** and the heating member **54b3**. Therefore, even after the maximum amount of power is reduced, the temperature of the heater **54** does not decrease, the temperature in the center portion of the heater **54** with respect to the longitudinal direction tracks the target temperature, and the image defects due to insufficient temperature of the fixing device **50** are not occurred. Further, temperature rise, in the paper non-passage area of the fixing nip portion N with respect to the longitudinal direction through which the A5 size paper P does not pass, is kept within a certain range, and image defects at edge portions of the A5 size paper P due to excessive heat are not occurred.

(79) As described above, according to the embodiment, it is possible to switch the power supply to the heater from the control in which power is supplied to one heating member to the control in which power is supplied to a plurality of the heating members alternately, based on the detected temperature according to a condition of the fixing device.

Second Embodiment

(80) In the first embodiment, when the detected temperature of the heater by the fixing temperature sensor reached the threshold temperature, the switching control of the power supply to the heating member is started. In a second embodiment, an embodiment, in which the switching control of the power supply to the heating member is started when the detected temperature of the heater by the fixing temperature sensor achieves the threshold temperature and a leading edge of the paper reaches the fixing nip portion, will be described.

Incidentally, constitutions of the image forming apparatus and the fixing device **50** are similar to the first embodiment, same reference numerals in the first embodiment are used for the same devices and members, and descriptions are omitted.

(81) [Control Sequence for the Power Supply to the Heating Members]

(82) FIG. **10** is a flowchart showing a control sequence for performing the power supply to the heating members **54b1** and **54b3** when executing the print job which prints the A5 size paper P. A process which is shown in FIG. **10** is launched when a print job is started and executed by the CPU **94**. The power supply periods to the heating members **54b1** and **54b3** are determined based on the usage ratio (which is also the power supply ratio) of the heating members **54b1** and **54b3** according to the zones which corresponds to the count values which are shown in Table 1 described above. Incidentally, updating of the count value which determines the zone is performed in a separate process.

(83) A process of **S200** is similar to a process of **S100** in FIG. **7** of the first embodiment, and a description is omitted here. In **S201**, the CPU **94** determines whether the leading edge of the A5 size paper P reaches the fixing nip portion N. In the embodiment, the CPU **94** calculates a time required for the paper P to reach the fixing nip portion N based on a distance of a feeding passage from the cassette **16** to the fixing nip portion N and a feeding speed of the paper P, and also reset and start the timer. And the CPU **94** determines whether or not the paper P reaches the fixing nip portion N by whether or not the required time is elapsed with reference to the timer. Incidentally, the distance of the feeding passage from the cassette **16** to the fixing nip portion N and the feeding speed of the paper P is stored in the memory **95** in advance. In a case that the CPU **94** determines that the required time is elapsed by referring to the timer, the CPU **94** determines that the paper P reaches the fixing nip portion N and proceeds the process to **S202**. On the other hand, in a case that the CPU **94** determines that the required time is not elapsed, the CPU **94** determines that the paper P does not reach the fixing nip portion N and returns the process to **S201**. Processes from **S202** through **S208** are similar to the processes from **S101** through **S107** in FIG. **7** of the first embodiment, and a description is omitted here. Incidentally, the order of the processes **S201** and **S202** may be reversed.

(84) [Timing of Starting of Switching of Heating Members]

(85) Next, a timing of starting of the switching of heating members when paper is passed through in the embodiment will be described. FIG. **11** is a diagram illustrating a relationship between the heating member in which the power supply is performed at a power source voltage of 120V and the detected temperature by the fixing temperature sensor **59** during printing of the A5 size paper P in the zone 4. FIG. **11** is the diagram which

is a similar constitution of FIG. 8, and an explanation of a view of the figure is omitted. Incidentally, the target temperature of the heater **54** is 220° C., which is same as in the first embodiment. Further, the threshold temperature of the heater **54** (described as a thermistor threshold temperature in the graph) which starts the switching control of the heating members **54b1** and **54b3** is 210° C.

(86) In the embodiment, the heater **54** is heated by the heating member **54b1** whose length is long with respect to the longitudinal direction and, after the fixing temperature sensor **59** detects that the temperature of the heater **54** has reached the threshold temperature, a control in which the heating member **54b1** and the heating member **54b3** whose length is short with respect to the longitudinal direction are alternately switched, is performed. First, a warmup operation to heat the fixing device **50** is started at a same time as the printing operation is started. Specifically, as the start of the printing operation, the power supply to the heating member **54b1** and the rotating operation of the pressing roller **53** start. As shown in a graph of FIG. 11, four seconds after the start of the printing operation, the detected temperature (the thermistor detection temperature) of the heater **54** by the fixing temperature sensor **59** reaches at 210° C. which is the thermistor threshold temperature. And 4.5 seconds after the start of printing operation, the leading edge of the A5 size paper P reaches the fixing nip portion N, and the control of switching the power supply of the heating member **54b1** and the heating member **54b3** alternately is started. In this way, in the second embodiment, unlike the first embodiment, even when the detected temperature of the heater **54** by the fixing temperature sensor **59** reaches the thermistor threshold temperature, the heating member switching control does not start until the A5 size paper P reaches the fixing nip portion N.

(87) As described above, when the switching control of the heating members is performed while the paper P is not passing through the fixing nip portion N, the temperature in the end portion of the fixing nip portion N with respect to the longitudinal direction decreases compared to the center portion of the fixing nip portion N with respect to the longitudinal direction. Further, when the switching control of the heating members is started, the maximum amount of power which is possible to supply to the heater **54** is decreased, so the timing of reaching the target temperature of the heater **54** may be delayed. In the embodiment, during the warmup of the fixing device **50**, the power supply switching control to the heating members is started after the paper P reaches the fixing nip portion N, so it is possible to prevent from decreasing the temperature in the end portions of the heater **54** with respect to the longitudinal direction. Further, a condition, that the maximum amount of power which is possible to supply to the heater **54** is large, is maintained for a longer period of time, so the timing that the heater **54** reaches the target temperature is earlier. Further, in a case that the power source voltage is as low as 110V and the temperature of the heater **54** does not reached the thermistor threshold temperature when the leading edge of the paper P reaches the fixing nip portion N, same control may be performed as described by using FIG. 9 in the first embodiment. Therefore, the temperature decrease in the center portion of the heater **54** with respect to the longitudinal direction is suppressed, the temperature rise at the edge portion with respect to the longitudinal direction also falls within a certain range, and image defects are not occurred at the edge portions of the A5 size paper P due to excessive heat. In the embodiment, in addition to the effects of the first embodiment, it is possible to prevent the temperature decrease in the end portions of the fixing nip portion N with respect to the longitudinal direction during the warmup of the fixing device **50** and the timing of reaching the target temperature during the warmup is also possible to be earlier.

(88) As described above, according to the embodiment, it is possible to switch the power supply to the heater from the control in which power is supplied to one heating member to the control in which power is supplied to the plurality of the heating members alternately, based on the detected temperature according to the condition of the fixing device.

Third Embodiment

(89) In a third embodiment, an embodiment, in which the temperature control of the fixing device is precisely controlled by correcting the threshold temperature (which is also referred to as the thermistor threshold temperature) at which the switching control of the heating members is started according to an environmental temperature and the power source voltage of the image forming apparatus and basis weight of the paper which is used, will be described.

(90) [Control Block of the Image Forming Apparatus]

(91) FIG. 12 is a block diagram showing a constitution of a control portion in the image forming apparatus of the embodiment. In FIG. 12, compared to FIG. 2 in the first embodiment, an environmental temperature sensor **106** and an electric current detecting circuit **107** are added. Other members and devices are same as those which are shown in FIG. 2 of the first embodiment, and descriptions in here are omitted by using same reference numerals for the same members and devices.

(92) The environmental temperature sensor **106**, which is a second temperature detecting unit, is provided at a position in which it is not affected by heat which is generated by the heater **54** of the fixing device **50**, detects

ambient temperature of the image forming apparatus (hereinafter referred to as “environmental temperature”), and outputs detected environmental temperature to the CPU **94**. Further, the fixing power control device **97** includes the electric current detecting circuit **107**. The electric current detecting circuit **107** detects electric current which is supplied from the AC power source **55** to the heater **54** of the fixing device **50** and outputs the detected electric current value to the CPU **94**.

(93) [Power Control Circuit]

(94) FIG. **13** is a schematic diagram showing a constitution of the power control circuit of the fixing device **50** in the embodiment. FIG. **13** is different from FIG. **6** in the first embodiment in that the electric current detecting circuit **107** is added. Other circuits and members which are shown in FIG. **13** are same as those shown in FIG. **6** of the first embodiment, and descriptions are omitted by using same reference numerals for same circuits and members. The electric current detecting circuit **107** is provided in an electric current passage between the AC power source **55** and the triacs **56a** and **56b**, and detects electric current value which is supplied to the heating members of the heater **54** in the fixing device **50**. The electric current detecting circuit **107** outputs a detected result of the current value to the CPU **94**.

(95) [Calculation of the Power Source Voltage]

(96) The CPU **94** calculates the power source voltage, which is value of AC voltage which is supplied from the AC power source **55**, based on the electric current value which is obtained from the electric current detecting circuit **107**. FIG. **14** is a flowchart showing a voltage calculation sequence in which the CPU **94** calculates the power source voltage. A process in FIG. **14** is started when a power source of the image forming apparatus is turned on and is executed by the CPU **94**. Incidentally, the memory **95** stores a resistance value of the heating member **54b1** which is measured in advance.

(97) When the power source of the image forming apparatus is turned on, the power supply is performed to the fixing device **50**, and an operation of rotating the pressing roller **53** (pre multiple rotation) is performed. In **S31**, the CPU **94** turns on the triac **56a** and turns off the triac **56b** during pre multiple rotation, and the power supply is performed from the AC power source **55** to the heating member **54b1** at 80% of a duty cycle. In **S32**, the CPU **94** obtains an electric current value I which is output from the AC power source **55**, from the electric current detecting circuit **107**. In **S33**, the CPU **94** obtains a resistance value R of the heating member **54b1** from the memory **95**. In **S34**, the CPU **94** calculates the power source voltage V (=the electric current value $I \times$ the resistance value R) which is supplied from the AC power source **55** by using the electric current value I which is obtained in **S32** and the resistance value R which is obtained in **S33**, stores the calculated power source voltage V in the memory **95**, and finishes the process. Incidentally, in the embodiment, the power source voltage is obtained based on the electric current value I and the resistance value R which are measured, however, for example, the power source voltage may be estimated by a state of temperature rise of the heater **54** which is detected by the fixing temperature sensor **59** with respect to the amount of power which is supplied to the heater **54**.

(98) [Correction of the Thermistor Threshold Temperature]

(99) In the embodiment, in order to precisely control the temperature of the fixing device **50**, the threshold temperature (thermistor threshold temperature) at which the switching control of the heating members is started is corrected according to the environmental temperature and the power source voltage of the image forming apparatus and the basis weight of the paper which is used. Here, the thermistor threshold temperature at which the switching control of the heating members which are described in the first embodiment and the second embodiment is started is a reference thermistor threshold temperature T_a (unit: ° C.), and an amount of correction of correcting the reference thermistor threshold temperature T_a is an amount of thermistor threshold correction T_b (unit: ° C.). And when the thermistor threshold temperature after correction is a thermistor threshold temperature T_s (unit: ° C.), the thermistor threshold temperature T_s in the embodiment is described as a following (equation 1).

Thermistor threshold temperature T_s = Reference thermistor threshold temperature T_a + The amount of thermistor threshold correction T_b (equation 1)

(100) The reference thermistor threshold temperature T_a is determined by the environmental temperature T (unit: ° C.) which is detected by the environmental temperature sensor **106** and the power source voltage V (unit: V) which is calculated by the voltage calculation sequence which is described above and is described as a following (equation 2).

Reference thermistor threshold temperature $T_a = 220 - (\text{Environmental Temperature } T - 23) - (\text{Power supply voltage } V - 120) / 2$ (equation 2)

(101) As described above, the higher the environmental temperature T is above a predetermined temperature (23° C.), the lower the reference thermistor threshold temperature T_a is. This is because the higher the

environmental temperature T is above the predetermined temperature (23° C.), the more allowance there is for the temperature decrease in the center portion of the heater **54** with respect to the longitudinal direction. Further, the higher the power source voltage V is above a predetermined voltage (120 V), the lower the reference thermistor threshold temperature Ta is. Because the higher the power source voltage V is than the predetermined voltage (120 V), the higher the maximum amount of power which is supplied to the heater **54**, and the temperature in the center portion of the heater **54** with respect to the longitudinal direction is not easily decreased even when the switching control of the heating members is started at a lower temperature.

(102) Further, the amount of thermistor threshold correction Tb changes depending on the basis weight (weight per unit area) of the paper P. Table 2 is a table showing a relationship between the basis weight X of the paper P and the amount of the thermistor threshold correction Tb, and the amount of the thermistor threshold correction Tb (unit: ° C.) according to the basis weight X of the paper P (unit: g/m.sup.2) is shown.

(103) TABLE-US-00002 TABLE 2 Amount of thermistor threshold correction Tb [° C.] Basis weight X (g/m.sup.2) X = 60 -5 60 < X ≤ 75 0 75 < X ≤ 90 +5

(104) As shown in Table 2, the larger the basis weight X, the larger the amount of the thermistor threshold correction Tb. Because the smaller the basis weight of the paper P is, the less heat is taken from (the fixing nip portion N of) the fixing device **50** when the paper P is passing through the fixing nip portion N. This is because the temperature in the center portion of the fixing nip portion N with respect to the longitudinal direction is not easily decreased, even when the switching control of the heating members is started at a lower temperature. A method of calculating the thermistor threshold temperature Ts in the embodiment by (equation 1) which is described above is confirmed by experimentally changing the environmental temperature T, the power source voltage V and the basis weight X of the paper P.

(105) For example, in a case that the environmental temperature T is 30° C., the power source voltage V is 110V, and the basis weight of the A5 size paper P is 80 g/m.sup.2, the reference thermistor threshold temperature Ta is calculated by using (equation 2) as below.

$$(106) \quad \begin{aligned} \text{Referencethermistor} \\ \text{thresholdtemperatureTa} \end{aligned} &= 200 - (30 - 23) - (110 - 120) / 2 \\ &= 218(\text{unit: } ^\circ\text{C.}) \end{aligned}$$

Further, the amount of the thermistor threshold correction Tb (unit: ° C.) is +5° C. from Table 2. Therefore, the thermistor threshold temperature Ts is calculated by (equation 1) as below.

$$(107) \quad \begin{aligned} \text{Thermistorthreshold} \\ \text{temperatureTa} \end{aligned} &= \begin{aligned} \text{Referencethermistorthreshold} \\ \text{temperatureTa} \end{aligned} + \\ &\quad \begin{aligned} \text{Amountofthermistorthreshold} \\ \text{correctionTb} \end{aligned} \\ &= 218 + 5 = 223(\text{unit: } ^\circ\text{C.}) \end{aligned}$$

(108) As described above, in the embodiment, the thermistor threshold temperature Ts is obtained as an absolute value, however, it may be a value relative to the target temperature of the heater **54**, for example. Further, in the embodiment, the thermistor threshold temperature Ts is corrected according to the basis weight of the paper P, however, the thermistor threshold temperature Ts may be corrected based on an index which indicates other properties of the paper P such as a surface roughness of the paper P. As described above, in addition to the effects in the second embodiment which is described above, in the embodiment, the thermistor threshold temperature is finely corrected according to the environmental temperature, the power source voltage and the basis weight of the paper. Therefore, it is possible to control temperature more precisely so that temperature of the heater in the center portion with respect to the longitudinal direction is appropriate while temperature of the fixing nip portion N in the end portions with respect to the longitudinal direction is also appropriate.

(109) As described above, according to the embodiment, it is possible to switch the power supply to the heater from the control in which power is supplied to one heating member to the control in which power is supplied to the plurality of the heating members alternately, based on the detected temperature according to the condition of the fixing device.

Fourth Embodiment

(110) In a fourth embodiment, an embodiment in which switching control of the heating member is started, after the heater temperature reaches the threshold temperature (thermistor threshold temperature) at which the switching control of the heating member is started and a waiting time which is set according to the environmental temperature, the power source voltage and the basis weight of the paper, will be described. Incidentally, constitutions of the image forming apparatus and the fixing device **50** are similar to the third

embodiment, same reference numerals in the third embodiment are used for the same devices and members, and descriptions are omitted.

(111) [Calculation of Waiting Time]

(112) In a case that the switching of the heating members is started immediately after the heater **54** reaches the target temperature, since a heat storage amount of the fixing device is not enough, temperature in the center portion of the fixing nip portion N with respect to the longitudinal direction decreases when the amount of average power which is supplied to the heater **54** by the switching control of the heating members decreases. As a result, image defects may occur due to insufficient heat from the heater **54**. For example, in a case that the environmental temperature T of the image forming apparatus is low, an amount of heat radiation from the heater **54** is greater compared to a case that the environmental temperature T is high, so temperature may decrease in the center portion of the heater **54** with respect to the longitudinal direction. Further, in a case that the power source voltage V which is supplied from the AC power source **55** is low, since the maximum amount of power in which the AC power source **55** is able to output is low, temperature may decrease in the center portion of the heater **54** with respect to the longitudinal direction. Furthermore, in a case that the basis weight of the paper P is large, since an amount of heat in the fixing nip portion N which is taken by the paper P while the paper P is passed through the fixing nip portion N is large, temperature may decrease in the center portion of the fixing nip portion N with respect to the longitudinal direction. In the embodiment, in a case that the environmental temperature T is low, a case that the power source voltage V is low, or a case that the basis weight of the paper P is large, as described above, a waiting time until the switching control of the heating member after the heater **54** reaches the target temperature is set. Therefore, the fixing device **50** stores heat with a sufficient amount of power and temperature decrease in the center portion of the fixing nip portion N with respect to the longitudinal direction is suppressed.

(113) [Calculation of Waiting Time]

(114) Next, a method for calculating waiting time Tw from a time when the heater **54** reaches the target temperature until a time when the switching control of the heating member is started, will be described. When a reference waiting time is defined as a reference waiting time Tn (unit: second), and a correction amount to correct the reference waiting time Tn is defined as a waiting time correction amount Tm (unit: second), a waiting time Tw (unit: second) is described as a following (equation 3).

(115) $\text{WaitingtimeTw} = \text{ReferencewaitingtimeTn} + \text{WaitingtimecorrectionamountTm}$ (equation3)

(116) The reference waiting time Tn is determined by the environmental temperature T (unit: ° C.) which is detected by the environmental temperature sensor **106** and the power source voltage V (unit: V) which is calculated by the voltage calculation sequence which is described in the third embodiment and described as a following (equation 4).

(117) $\text{ReferencewaitingtimeTn} = 2 - (\text{EnvironmentaltemperatureT} - 23) / 7 - (\text{PowersourcevoltageV} - 120) / 14$ (Equation4)

(118) Further, waiting time correction amount Tm is changed by the basis weight (weight per unit area) of the paper P. Table 3 is a table showing a relationship between the basis weight X of the paper P and the waiting time correction amount Tm, and the waiting time correction amount Tm (unit: second) according to the basis weight X of the paper P (unit: g/m.sup.2).

(119) TABLE-US-00003 TABLE 3 Amount of standby time correction Tm [sec] Basis weight X (g/m.sup.2) X = 60 -0.5 60 < X ≤ 75 0 75 < X ≤ 90 +0.5

(120) Further, the waiting time Tw is limited to between 0 and 4 seconds. The calculation method of the waiting time Tw by (equation 3) which is described above, is experimentally confirmed by changing the environmental temperature, the power source voltage and the basis weight of the paper P.

(121) For example, in a case that the environmental temperature T is 30° C., the power source voltage Vis 110V and the basis weight of the A5 size paper P is 80 g/m.sup.2, the reference waiting time Tn is calculated by using (equation 4) as follows.

(122) $\text{ReferencewaitingtimeTn} = 1 - (30 - 23) / 7 - (110 - 120) / 14$
 $= 0.71(\text{second})$

Further, the waiting time correction amount Tm (unit: second) is +0.5 seconds from Table 3. Therefore, the waiting time Tw is calculated from (equation 3).

(123) $\text{WaitingtimeTw} = 0.71 + 0.5 = 1.21(\text{unit: second})$

[Control Sequence for the Power Supply to the Heating Members]

(124) FIG. 15 is, in the embodiment, a flowchart showing a control sequence for performing the power supply to the heating members **54b1** and **54b3** when executing the print job which prints the A5 size paper P. A process in

FIG. 15 is illustrated when the print job is started, and is executed by the CPU 94. The power supply periods to the heating members 54b1 and 54b3 are determined based on the usage ratio (which is also the power supply ratio) of the heating members 54b1 and 54b3 according to the zones which corresponds to the count values which are shown in Table 1 described above. Incidentally, updating of the count value which determines the zone is performed in a separate process. Further, the power source voltage V, which is calculated by the voltage calculation sequence which is described in the third embodiment, is stored in the memory 95. Furthermore, data in Table 3, which is a table showing the relationship between the basis weight X of the paper P and the waiting time correction amount Tm which is described above, are stored in the memory 95. Further, the basis weight of each size of the paper P is stored in the memory 95.

(125) Processes from S400 to S402 are similar to processes from S200 to S202 in FIG. 10 of the second embodiment, and descriptions are omitted here. In S403, the CPU 94 calculates the waiting time Tw which is described above. In detail, the CPU 94 obtains the environmental temperature T which is detected by the environmental temperature sensor 106, obtains the power source voltage V from the memory 95 and calculates the reference waiting time Tn by using (equation 4) described above. Furthermore, the CPU 94 determines the waiting time correction amount Tm based on the data in Table 3 which is stored in the memory 95 and the basis weight of the A5 size paper P, and calculates the waiting time Tw by using (equation 3) described above.

(126) In S404, the CPU 94 resets and starts the timer. In S405, the CPU 94 refers to the timer and determines whether the waiting time Tw is elapsed. In a case of determining that the waiting time Tw is elapsed, the CPU 94 proceeds the process to S406, and in a case of determining that the waiting time Tw is not elapsed, the CPU 94 returns the process to S405. Processes from S406 to S411 are similar to processes from S203 to S208 in FIG. 10 of the second embodiment, and descriptions are omitted here.

(127) In this way, in addition to effects of the second embodiment, it is possible to perform the temperature control of the heater 54 accurately, by setting a waiting time until the switching control of the heating member is started after reaching the thermistor threshold temperature. Further, it is possible to perform the temperature control of the heater 54 more accurately by finely changing the waiting time according to the environmental temperature, the power source voltage and the basis weight of the paper.

(128) As described above, according to the embodiment, it is possible to switch the power supply to the heater from the control in which power is supplied to one heating member to the control in which power is supplied to the plurality of the heating members alternately, based on the detected temperature according to the condition of the fixing device.

(129) According to the present invention, it is possible to switch the power supply to the heater from the control in which power is supplied to one heating member to the control in which power is supplied to the plurality of the heating members alternately, based on the detected temperature according to the condition of the fixing device.

Other Embodiment(s)

(130) Embodiment(s) of the present invention can also be realized by a computer of a system or apparatus that reads out and executes computer executable instructions (e.g., one or more programs) recorded on a storage medium (which may also be referred to more fully as a 'non-transitory computer-readable storage medium') to perform the functions of one or more of the above-described embodiment(s) and/or that includes one or more circuits (e.g., application specific integrated circuit (ASIC)) for performing the functions of one or more of the above-described embodiment(s), and by a method performed by the computer of the system or apparatus by, for example, reading out and executing the computer executable instructions from the storage medium to perform the functions of one or more of the above-described embodiment(s) and/or controlling the one or more circuits to perform the functions of one or more of the above-described embodiment(s). The computer may comprise one or more processors (e.g., central processing unit (CPU), micro processing unit (MPU)) and may include a network of separate computers or separate processors to read out and execute the computer executable instructions. The computer executable instructions may be provided to the computer, for example, from a network or the storage medium. The storage medium may include, for example, one or more of a hard disk, a random-access memory (RAM), a read only memory (ROM), a storage of distributed computing systems, an optical disk (such as a compact disc (CD), digital versatile disc (DVD), or Blu-ray Disc (BD)?), a flash memory device, a memory card, and the like.

(131) While the present invention has been described with reference to exemplary embodiments, it is to be understood that the invention is not limited to the disclosed exemplary embodiments. The scope of the following claims is to be accorded the broadest interpretation so as to encompass all such modifications and equivalent structures and functions.

Claims

1. An image forming apparatus comprising: an image forming unit configured to form an unfixed toner image on a recording material; and a fixing unit for fixing the unfixed toner image on the recording material, wherein the fixing unit comprises: a first rotatable member; a heater provided, on a substrate, with a plurality of heat generating members, including a first heat generating member and a second heat generating member of which a length in a longitudinal direction is shorter than a length of the first heat generating member, and configured to heat the first rotatable member; a first temperature detecting unit configured to detect a temperature of the heater; a second rotatable member configured to form a nip portion with the first rotatable member; a switching unit configured to switch a power supply path from an AC power source to the first heat generating member or the second heat generating member; a control unit configured to control the switching unit to supply power to the first heat generating member or the second heat generating member, wherein when the control unit receives a print command to the recording material of which a length in a widthwise direction corresponds to the length of the second heat generating member, the control unit executes a first control in which the switching unit supplies the power only to the first heat generating member until the temperature detected by the first temperature detecting unit reaches a threshold temperature from receiving the print command, and switches a second control in which the switching unit supplies the power alternately to the first heat generating member or the second heat generating member after the temperature detected by the first temperature detecting unit reaches the threshold temperature.
2. An image forming apparatus according to claim 1, further comprising a temperature predicting unit configured to predict a temperature of the fixing device based on a count value which is increased when the recording material passes through the nip portion and is decreased with a lapse of time when the recording material does not pass through the nip portion, wherein the threshold temperature is determined based on the count value of the temperature predicting unit.
3. An image forming apparatus according to claim 2, wherein the threshold temperature becomes lower as the count value of the temperature predicting unit becomes larger.
4. An image forming apparatus according to claim 3, wherein a time ratio supplying the power to the first heat generating member and the second heat generating member from the AC power source is determined based on the count value.
5. An image forming apparatus according to claim 1, wherein the control unit starts the second control when the temperature detected by the first temperature detecting unit reaches the threshold temperature and the recording material reaches the nip portion.
6. An image forming apparatus according to claim 1, wherein the heater provided with a third heat generating member of which a length in the longitudinal direction is shorter than the length of the second heat generating member; and a fourth heat generating member of which a length in the longitudinal direction is substantially equal to the length of the first heat generating member, and wherein the first heat generating member, the second heat generating member, the third heat generating member and the fourth heat generating member are arranged in this order with respect to a short side direction of the substrate.
7. An image forming apparatus according to claim 6, wherein the heater provided with a first contact point electrically connected to one end of the first heat generating member, the second heat generating member and the fourth heat generating member, a second contact point electrically connected to one end the third heat generating member, a third contact point electrically connected to the other ends of the second heat generating member and the third heat generating member, and a fourth contact point electrically connected to the other ends of the first heat generating member and the fourth heat generating member.
8. An image forming apparatus according to claim 7, wherein the switching unit includes a first switch, a second switch and a first relay, wherein the first switch connects or disconnects the AC power source and the fourth contact point, wherein the second switch connects or disconnects the AC power source and the first relay, and the AC power source and the second contact point, and wherein the first relay is capable of switching connection of the second switch and the third contact point, and connection of the AC power source and the third contact point.
9. An image forming apparatus according to claim 8, further comprising a detecting portion configured to detect a state of the first switch and the second switch; and a second relay configured to connect or disconnect a power supply path between the AC power source and the first contact point, wherein the detecting portion drives the

second relay to disconnect the power supply path when detecting a state in which the first switch connects the AC power source and the fourth contact point and the second switch connects the AC power and the first relay.

10. An image forming apparatus according to claim 9, wherein the first switch and the second switch include a bidirectional thyristor.

11. An image forming apparatus according to claim 10, wherein the first temperature detecting unit includes a thermistor.

12. An image forming apparatus according to claim 1, wherein the first rotatable member includes a cylindrical film, wherein the second rotatable member includes a pressing roller forming the nip portion in corporation with the film, and wherein the heater is arranged in an internal space of the film, the heater and the pressing roller nips the film, and the image on the recording material is heated at the nip portion via the film.

13. An image forming apparatus according to claim 1, further comprising a current detecting unit configured to detect a current supplied to the fixing device from the AC power source, wherein the threshold temperature is corrected based on a power supply voltage calculated based on a current value detected by the current detecting unit.

14. An image forming apparatus according to claim 1, wherein the threshold temperature is corrected to be higher in a case that the power supply voltage is lower than a predetermined voltage and to be lower in a case that the power supply voltage is higher than the predetermined voltage.

15. An image forming apparatus according to claim 1, wherein the threshold temperature is corrected to be lower in a case that a basis weight of the recording material is smaller than a predetermined basis weight and to be higher in a case that the basis weight of the recording material is larger than the predetermined basis weight.

16. An image forming apparatus according to claim 1, wherein the control unit starts the second control when a waiting time elapses after the temperature detected by the first temperature detecting unit reaches the threshold temperature and the recording material reaches the nip portion.

17. An image forming apparatus according to claim 16, further comprising a current detecting unit configured to detect a current supplied to the fixing device from the AC power source, wherein the waiting time is corrected based on a power supply voltage calculated based on a current value detected by the current detecting unit.

18. An image forming apparatus according to claim 16, wherein the waiting time is corrected to be longer in a case that the power supply voltage is lower than a predetermined voltage and to be shorter in a case that the power supply voltage is higher than the predetermined voltage.

19. An image forming apparatus according to claim 16, wherein the waiting time is corrected to be shorter in a case that a basis weight of the recording material is smaller than a predetermined basis weight and to be longer in a case that the basis weight of the recording material is larger than the predetermined basis weight.
