

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250279323

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

AUSTRIA; Jomari et al.

SENSOR PACKAGES

Abstract

In examples, semiconductor package comprises a semiconductor die having a device side including circuitry; a sensor on the device side; a metal ring on the device side to at least partially define a cavity vertically aligned with the sensor, with the metal ring having a top metal ring surface facing away from the semiconductor die and an exterior metal ring surface facing away from the sensor; and a metal pillar on the device side and having a top metal pillar surface facing away from the semiconductor die. The package also comprises a tie bar extending approximately parallel to the device side of the semiconductor die and coupled with solder to the top metal ring surface, with the tie bar exposed to a first exterior surface of the package. The package comprises a conductive member including a conductive terminal exposed to a second exterior surface of the package, a vertical member coupled to the conductive terminal and extending toward the first exterior surface of the package, and a horizontal member coupled to the vertical member, with the horizontal member soldered to the top metal pillar surface. The package comprises a mold compound contacting the exterior metal ring surface, with the mold compound absent from the cavity.

Inventors: AUSTRIA; Jomari (Malabon City, PH), DE ASIS; Ray Fredric (Mabalacat, PH)

Applicant: TEXAS INSTRUMENTS INCORPORATED (Dallas, TX)

Family ID: 96880480

Appl. No.: 18/592090

Filed: February 29, 2024

Publication Classification

Int. Cl.: H01L23/18 (20060101); H01L23/00 (20060101); H01L23/495 (20060101);
H01L25/065 (20230101)

U.S. Cl.:

CPC **H01L23/18** (20130101); **H01L23/49551** (20130101); **H01L23/49575** (20130101);
H01L24/16 (20130101); **H01L24/40** (20130101); **H01L24/73** (20130101);
H01L25/0652 (20130101); H01L2224/16146 (20130101); H01L2224/16155 (20130101);
H01L2224/4013 (20130101); H01L2224/40145 (20130101); H01L2224/73205
(20130101); H01L2924/01029 (20130101); H01L2924/182 (20130101);
H01L2924/18301 (20130101)

Background/Summary

BACKGROUND

[0001] During manufacture, semiconductor chips (also commonly referred to as “dies”) are typically mounted on die pads of lead frames and are wire-bonded, clipped, or otherwise coupled to leads of the lead frame. Other devices may similarly be mounted on a lead frame pad. The assembly is later covered in a mold compound, such as epoxy, to protect the assembly from potentially damaging heat, physical trauma, moisture, and other deleterious factors. The finished assembly is called a semiconductor package or, more simply, a package. The leads are exposed to surfaces of the package and are used to electrically couple the packaged chip to devices outside of the chip.

SUMMARY

[0002] In examples, semiconductor package comprises a semiconductor die having a device side including circuitry; a sensor on the device side; a metal ring on the device side to at least partially define a cavity vertically aligned with the sensor, with the metal ring having a top metal ring surface facing away from the semiconductor die and an exterior metal ring surface facing away from the sensor; and a metal pillar on the device side and having a top metal pillar surface facing away from the semiconductor die. The package also comprises a tie bar extending approximately parallel to the device side of the semiconductor die and coupled with solder to the top metal ring surface, with the tie bar exposed to a first exterior surface of the package. The package comprises a conductive member including a conductive terminal exposed to a second exterior surface of the package, a vertical member coupled to the conductive terminal and extending toward the first exterior surface of the package, and a horizontal member coupled to the vertical member, with the horizontal member soldered to the top metal pillar surface. The package comprises a mold compound contacting the exterior metal ring surface, with the mold compound absent from the cavity.

[0003] A method for manufacturing a package comprises plating a metal ring on a device side of a semiconductor die to at least partially define a cavity, with the device side including circuitry and a sensor; plating a metal pillar on the device side of the semiconductor die; depositing solder on a top surface of the metal ring opposite the semiconductor die and on a top surface of the metal pillar; and using the solder on the top surface of the metal ring to couple the metal ring to a tie bar extending approximately parallel to the semiconductor die. The method comprises using the solder on the top surface of the metal pillar to couple the metal pillar to a conductive member having a horizontal member extending approximately parallel to the semiconductor die, with a vertical member extending away from the horizontal member, and a conductive terminal extending horizontally away from the semiconductor die. The method comprises applying a mold compound to the device side of the semiconductor die and to an exterior surface of the metal ring facing away from the sensor, with the mold compound absent from the cavity.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0004] FIG. 1 is a profile, cross-sectional view of a sensor semiconductor package, in accordance with various examples.

[0005] FIG. 2 is a top-down view of a sensor semiconductor package, in accordance with various examples.

[0006] FIG. 3 is a perspective, see-through view of a sensor semiconductor package, in accordance with various examples.

[0007] FIG. 4 is a perspective view of a sensor semiconductor package, in accordance with various examples.

[0008] FIG. 5 is a cross-sectional view of a metal pillar coupled to circuitry in a sensor semiconductor package, in accordance with various examples.

[0009] FIG. 6 is a flow diagram of a method for manufacturing a sensor semiconductor package, in accordance with various examples.

[0010] FIGS. 7A1-7M3 are a process flow in cross-sectional, top-down, and perspective views for manufacturing a sensor semiconductor package, in accordance with various examples.

[0011] FIG. 8 is a block diagram of an electronic device containing a sensor semiconductor package, in accordance with various examples.

DETAILED DESCRIPTION

[0012] Sensor packages are packages that include sensors configured to measure various properties in a variety of applications, such as temperature, humidity, pH, the presence of nucleic acids, etc. In sensor packages, a sensor is positioned on the chip, and a cavity in the mold compound extends down to the surface of the chip where the sensor is located. In this way, test material that is to be tested by the sensor (e.g., fluids) can enter the cavity and reach the sensor, thus permitting the sensor to detect one or more properties of that test material. The cavities are typically formed using a specially-designed mold chase that blocks mold compound from entering the space above the sensor. However, using a specially-designed mold chase for this purpose is an expensive and tedious endeavor, and further, it can be difficult to achieve proper alignment of the mold chase and the package components during mold compound application. In some cases, cavities are formed by electroplating a mushroom-shaped metal ring circumscribing the sensor. The top of the metal ring (i.e., the “cap” of the “mushroom”) contacts the mold chase when the mold chase is closed, thereby precluding mold compound from flowing into the cavity and onto the sensor. While such a mushroom-shaped metal ring obviates the need for specially-designed mold chases and mitigates the difficulty associated with aligning the mold chases and package components during mold compound application, the metal ring height must be greater than that of any bond wires in the package. Otherwise, the mold compound will not fully cover the bond wires, leaving the bond wires exposed outside of the package and vulnerable to damage. Film assists may also be necessary during mold compound application to prevent mold seepage.

[0013] This disclosure describes various examples of sensor packages having cavities formed by techniques that mitigate the technical challenges described above. In examples, a package includes a semiconductor die having a device side including circuitry. The package includes a sensor on the device side. The package includes a metal ring on the device side and encircling the sensor to define a cavity, where the metal ring has a top metal ring surface facing away from the semiconductor die and an exterior metal ring surface facing away from the sensor. The package includes a metal pillar on the device side and having a top metal pillar surface facing away from the semiconductor die. The package also comprises a tie bar extending approximately parallel to the device side of the semiconductor die and soldered to the top metal ring surface, with the tie bar exposed to a first exterior surface of the package. The package further includes a conductive member including a conductive terminal exposed to a second exterior surface of the package, a vertical member coupled to the conductive terminal and extending toward the first exterior surface

of the package, and a horizontal member extending approximately parallel to the device side of the semiconductor die. The horizontal member is soldered to the top metal pillar surface. The package also includes a mold compound contacting the exterior metal ring surface, where the mold compound is absent from the cavity.

[0014] The sensor semiconductor packages described herein are superior to packages containing metal rings with bond wires, because the examples herein leverage uniquely-designed lead frames that enable bond wires to be omitted from the semiconductor package. As a result, the vertical thickness (i.e., height) of the metal ring in the package is less compared to packages having bond wires, resulting in thinner, lighter, and less expensive sensor semiconductor packages. Further, in the sensor semiconductor packages described herein, it is easier to control the height and shape of the metal ring, as opposed to packages having the “mushroom”-style metal rings, the manufacture of which may entail a degree of uncertainty in the height and shape of the completed metal ring. Further, the sensor semiconductor packages described herein are superior to other solutions because the examples herein do not require special tooling and equipment (e.g., specially-designed mold chases, mold assists, etc.), thus significantly reducing manufacturing time, complexity, and expense.

[0015] FIG. 1 is a profile, cross-sectional view of a sensor semiconductor package, in accordance with various examples. In particular, FIG. 1 depicts a sensor semiconductor package **100** including a semiconductor die **102** having a device side **104** and a non-device side **106** opposite the device side **104**. The device side **104** has circuitry **108** formed therein. Although circuitry **108** is depicted as being positioned in two locations on the device side **104**, in practice, circuitry **108** may be distributed throughout the device side **104** as may be appropriate for the particular application in which the sensor semiconductor package **100** is deployed. A sensor **110** is also included on the device side **104** of the semiconductor die **102**. The sensor **110** may be configured to sense any suitable type of property, including temperature, humidity, pressure, light, chemical properties such as salinity, pH, etc. The sensor **110** is exposed to a surface of the device side **104**, meaning that the sensor **110** is directly accessible from outside of the semiconductor die **102**. A metal ring **112** is on the device side **104**. The metal ring **112** has an approximately uniform horizontal thickness (i.e., width) throughout its height, meaning that the metal ring **112** lacks the “mushroom” shape of other metal rings. Because bond wires are omitted from the sensor semiconductor package **100**, the loop heights of the bond wires are not at risk of not being covered and protected by mold compound, and thus the height of the metal ring **112** is not determined by bond wire loop heights. Accordingly, the height of the metal ring **112** may be reduced relative to other semiconductor packages that use bond wires. In turn, this reduction in the height of the metal ring **112** reduces overall sensor semiconductor package **100** thickness, weight, and cost.

[0016] Metal pillars **114** are coupled to the device side **104**, and, more particularly, to circuitry **108** on the device side **104**. Metal pillars **114** extend away from the device side **104** and toward a top surface of the sensor semiconductor package **100**. In examples, the metal pillars **114** have heights approximately the same as the height of the metal ring **112**. Solder **116** is on a top surface of the metal ring **112** that is distal to the device side **104**, and solder **118** sits on top surfaces of the metal pillars **114** that are distal to the device side **104**.

[0017] The sensor semiconductor package **100** comprises a tie bar **122** at the top surface of the sensor semiconductor package **100**. The tie bar **122** extends approximately parallel to the device side **104** of the semiconductor die **102**. The tie bar **122** includes a first component **126** (also referred to herein as a “tie bar ring **126**”) and second components **124**, **128**. The first component **126** is thicker than either of the second components **124**, **128**. The first component **126** is coupled to the metal ring **112** by the solder **116**. Together, the metal ring **112**, solder **116**, and the first component **126** define a cavity **113**. The sensor **110** is vertically aligned with the cavity **113**, meaning a vertical line orthogonal to the surface of the device side **104** extends through both the sensor **110** and the cavity **113**. The surface of the first component **126** that is exposed to the cavity

113 is approximately flush with the inner surface of the metal ring **112** that is exposed to the cavity **113**, thereby encouraging the flow of fluid and gases into and out of the cavity **113**. Like the metal ring **112** and the solder **116**, the first component **126** is ring-shaped and has approximately the same inner diameter and inner circumference as the metal ring **112** and the solder **116**. The second components **124**, **128** are linearly shaped, not ring-shaped, and extend away from the first component **126** in opposing directions, as shown. The tie bar **122** is exposed to the top surface of the sensor semiconductor package **100**, meaning that mold compound or other components of the sensor semiconductor package **100** do not cover the top surface **129** of the tie bar **122**. The tie bar **122** does not carry useful electrical signals.

[0018] The sensor semiconductor package **100** also includes conductive members **130**, which are configured to carry useful electrical signals. Each conductive member **130** includes a horizontal member **132**, a vertical member **134** coupled to the horizontal member **132**, and a conductive terminal **136** coupled to the vertical member **134**. The vertical member **134** has an outer surface **135**, and the conductive terminal **136** has a top surface **137**. The horizontal member **132** is coupled to one or more metal pillars **114** by solder **118**. The conductive terminal **136** is exposed to multiple exterior surfaces of the sensor semiconductor package **100**, such as lateral and bottom surfaces of the sensor semiconductor package **100**. A mold compound **138** covers the various components of the sensor semiconductor package **100** as shown, including all components described above except for the sensor **110**, portions of the semiconductor die **102**, the tie bar **122**, and portions of the metal ring **112**, solder **116**, and conductive terminal **136**, all as shown. Critically, mold compound **138** is not present in the cavity **113** and does not contact the inner surface of the metal ring **112**, but the mold compound **138** does contact the outer surface of the metal ring **112**, as shown. The mold compound **138** contacts the outer surface **135** of the vertical member **134** and the top surface **137** of the conductive terminal **136**.

[0019] FIG. 2 is a top-down view of the sensor semiconductor package **100**, in accordance with various examples. FIG. 3 is a perspective, see-through view of the sensor semiconductor package **100**, in accordance with various examples. FIG. 4 is a perspective view of the sensor semiconductor package **100**, in accordance with various examples. As can be seen from FIGS. 1-4, an entirety of the conductive member **130** is located farther from the top surface of the mold compound **138** (and, by extension, farther from the top surface of the sensor semiconductor package **100**) than is the tie bar **122**. The tie bar **122** is located closer to the top surface of the mold compound **138** (and the top surface of the sensor semiconductor package **100**) than is any part of the conductive member **130**. In FIG. 4, the completed sensor semiconductor package **100** is shown from a perspective view, with the mold compound **138** covering all components of the sensor semiconductor package **100** except for some surfaces of the tie bar **122** and the conductive terminals **136**. In particular, the second components **124**, **128** of the tie bar **122** are exposed to the top surface of the sensor semiconductor package **100**. In addition, the top surface of the tie bar ring **126** is exposed to the top surface of the sensor semiconductor package **100**. The tie bar ring **126** encircles the cavity **113**, as shown. Ends of the second components **124**, **128** of the tie bar **122** distal to the tie bar ring **126** are exposed to opposing lateral surfaces of the sensor semiconductor package **100**, as shown, which are the same lateral surfaces to which distal ends of the conductive terminals **136** are exposed. Exposure of the tie bar **122** in this manner is indicative of efficient architecture because the tie bar **122** provides mechanical support to the semiconductor die **102** through the metal ring **112**, eliminating the need for a die pad within the sensor semiconductor package **100**. Elimination of the die pad reduces manufacturing complexity, time, and cost, as well as sensor semiconductor package **100** size, weight, and cost. Thus, the tie bar **122** extending along the top of the sensor semiconductor package **100** in this manner represents efficient and useful design. Furthermore, that same positioning of the tie bar **122**, and in particular the shape and position of the tie bar ring **126**, prevents mold compound **138** from flowing into the cavity **113** during application of the mold compound **138**. Thus, the position and structure of the tie bar **122**

presents multiple technical advantages.

[0020] FIG. 5 is a cross-sectional view of a metal pillar coupled to circuitry in a sensor semiconductor package, in accordance with various examples. In particular, FIG. 5 shows the semiconductor die **102** having circuitry **108** formed therein. For example, the circuitry **108** shown in FIG. 5 may comprise back end of line (BEOL) circuitry. A planarized passivation layer **502** contacts and protects the circuitry **108** from deleterious external influences. Vias **500** extend through the planarized passivation layer **502** and couple the circuitry **108** to a metal (e.g., copper) member **504**. A polyimide layer **506** surrounds the metal member **504**. The metal pillar **114** extends through the polyimide layer **506** and toward the horizontal member **132** of the conductive member **130**. More specifically, the metal pillar **114** couples to the horizontal member **132** of the conductive member **130** by way of solder **118**. The mold compound **138** covers the various structures shown in FIG. 5 and described above.

[0021] The metal member **504** has a thickness ranging between 4 microns and 25 microns, with a thickness below this range being disadvantageous because of unacceptably poor current carrying ability, and with a thickness above this range being disadvantageous because of significantly diminishing returns in current carrying ability. The vias **500** have diameters ranging between 0.5 microns and 10 microns, with a diameter below this range being disadvantageous because of unacceptably high costs of patterning vias, and with a diameter above this range being disadvantageous because of unacceptably high inefficiencies in area usage. The BEOL circuitry **108** shown in FIG. 5 has a thickness ranging between 0.2 microns and 3 microns, with a thickness below this range being disadvantageous because of unacceptably low current carrying ability, and with a thickness above this range being disadvantageous because of significantly diminishing returns in current carrying ability. The polyimide layer **506** has a vertical thickness ranging between 2 microns and 50 microns, with a thickness below this range being disadvantageous because of unacceptably reduced stress buffering ability, and with a thickness above this range being disadvantageous because of unacceptably increased costs. The vertical thickness of the metal pillar **114** ranges from 10 microns to 80 microns, with thicknesses below this range being disadvantageous because a standoff is necessary to apply underfill when underfill is applied, and with thicknesses above this range being disadvantageous because of an unacceptable increase in form factor. The solder **118** comprises an alloy of tin (80-100%), silver (1-5%), copper (0-5%), and nickel (0-1%). Alternatively, the solder **118** may comprise bismuth-indium solder (e.g., Bi—In) or a bismuth-tin alloy (e.g., Bi-43Sn). The solder **118** has a vertical thickness ranging between 10 microns and 80 microns, with a thickness less than this range being disadvantageous because a standoff is necessary to apply underfill when underfill is applied, and with a thickness above this range being disadvantageous because of an unacceptable increase in form factor.

[0022] FIG. 6 is a flow diagram of a method **600** for manufacturing a sensor semiconductor package, such as the sensor semiconductor package **100**, in accordance with various examples. FIGS. 7A1-7L3 are a process flow in cross-sectional, top-down, and perspective views for manufacturing a sensor semiconductor package, such as the sensor semiconductor package **100**, in accordance with various examples. Accordingly, FIGS. 6 and 7A1-7L3 are now described in parallel.

[0023] The method **600** includes plating a metal ring on a device side of a semiconductor die to at least partially define a cavity (**602**). The device side includes circuitry and a sensor (**602**). The method **600** also includes plating a metal pillar on the device side of the semiconductor die (**604**). FIG. 7A1 is a profile, cross-sectional view of the semiconductor die **102** having the circuitry **108** and the sensor **110**, as described above with reference to FIG. 1. FIG. 7A2 is a top-down view of the structure of FIG. 7A1, in accordance with various examples. FIG. 7A3 is a perspective view of the structure of FIG. 7A1, in accordance with various examples.

[0024] FIG. 7B1 is a profile, cross-sectional view of the structure of FIG. 7A1, except with the addition of a photoresist layer **700** on the semiconductor die **102**. The thickness of the photoresist

layer **700** should be approximately 10% thicker than the target vertical thickness (i.e., height) of the metal ring **112** and the metal pillars **114**, to accommodate for any coplanarity variation across the wafer. A technical advantage to the method **600** and the process flow of FIGS. **7A1-7L3** is that the metal ring **112** and the metal pillars **114** have uniform height (vertical thickness), which means that they can be formed simultaneously, without additional equipment or process steps. To ensure a proper seal so that mold compound **138** does not flow into the cavity **113** during application of the mold compound **138**, the tie bar ring **126** is made thicker than the remainder of the tie bar **122**, such that the tie bar ring **126** extends downward to meet the solder **116** that has been applied to the top surface of the metal ring **112**. In this way, a proper seal protecting the cavity **113** from mold compound **138** is achieved in an efficient manner. FIG. **7B2** is a top-down view of the structure of FIG. **7B1**, in accordance with various examples. FIG. **7B3** is a perspective view of the structure of FIG. **7B1**, in accordance with various examples.

[0025] FIG. **7C1** is a profile, cross-sectional view of the structure of FIG. **7B1**, except with the addition of a patterned mask **702** above the photoresist layer **700**. The patterned mask **702** selectively permits light to reach the photoresist layer **700**, thereby selectively exposing the photoresist layer **700**. FIG. **7C2** is a top-down view of the structure of FIG. **7C1**, in accordance with various examples. FIG. **7C3** is a perspective view of the structure of FIG. **7C1**, in accordance with various examples.

[0026] FIG. **7D1** is a profile, cross-sectional view of the structure of FIG. **7C1**, except that portions **704** of the photoresist layer **700** have been exposed to light. FIG. **7D2** is a top-down view of the structure of FIG. **7D1**, in accordance with various examples. FIG. **7D3** is a perspective view of the structure of FIG. **7D1**, in accordance with various examples.

[0027] FIG. **7E1** is a profile, cross-sectional view of the structure of FIG. **7D1**, except that the photoresist layer **700** has been developed (e.g., using an appropriate developer solution), thereby removing the exposed portions **704** that were depicted in FIG. **7D1** and forming cavities **706**, **708**. In addition, the patterned mask **702** has been removed. FIG. **7E2** is a top-down view of the structure of FIG. **7E1**, in accordance with various examples. FIG. **7E3** is a perspective view of the structure of FIG. **7E1**, in accordance with various examples.

[0028] FIG. **7F1** is a profile, cross-sectional view of the structure of FIG. **7E1**, except that metal pillars **114** and the metal ring **112** have been plated in the cavities **706**, **708**, respectively. FIG. **7F2** is a top-down view of the structure of FIG. **7F1**, in accordance with various examples. FIG. **7F3** is a perspective view of the structure of FIG. **7F1**, in accordance with various examples.

[0029] FIG. **7G1** is a profile, cross-sectional view of the structure of FIG. **7F1**, except that the photoresist layer **700** has been stripped away. FIG. **7G2** is a top-down view of the structure of FIG. **7G1**, in accordance with various examples. FIG. **7G3** is a perspective view of the structure of FIG. **7G1**, in accordance with various examples.

[0030] The method **600** also includes depositing solder on a top surface of the metal ring opposite the semiconductor die and on a top surface of the metal pillar (**606**). FIG. **7H1** is a profile, cross-sectional view of the structure of FIG. **7G1**, except that solder **116**, **118** has been deposited on the top surfaces of the metal ring **112** and the metal pillars **114**, respectively. FIG. **7H2** is a top-down view of the structure of FIG. **7H1**, in accordance with various examples. FIG. **7H3** is a perspective view of the structure of FIG. **7H1**, in accordance with various examples. FIG. **7I1** indicates that the structure of FIG. **7H1** may be prepared for coupling to a lead frame, for example, by re-orienting the structure in three-dimensional space. FIG. **7I2** is a top-down view of the structure of FIG. **7I1**, in accordance with various examples. FIG. **7I3** is a perspective view of the structure of FIG. **7I1**, in accordance with various examples.

[0031] The method **600** includes using the solder to couple the metal ring to a tie bar extending approximately parallel to the semiconductor die (**608**). The method **600** also includes using the solder to couple the metal pillar to a conductive member having a horizontal member extending approximately parallel to the semiconductor die, a vertical member extending away from the

horizontal member, and a conductive terminal extending horizontally away from the semiconductor die (**610**). FIG. **7J1** is a top-down view of a lead frame strip **710** having four lead frames **712** coupled to each other. Each lead frame **712** includes the tie bar **122** and multiple conductive members **130**. FIG. **7J2** is a perspective view of the structure of FIG. **7J1**, in accordance with various examples. FIG. **7J3** is a profile, cross-sectional view of the structure of FIG. **7I1** being coupled to a lead frame **712**. FIG. **7J4** is a top-down view of the structure of FIG. **7J3**, in accordance with various examples. FIG. **7J5** is a perspective view of the structure of FIG. **7J3**, in accordance with various examples.

[0032] FIG. **7K1** is a profile, cross-sectional view of the structure of FIG. **7J3**, except that the solder **116**, **118** has made contact with the tie bar **122** and the multiple conductive members **130** and reflowed. FIG. **7K2** is a top-down view of the structure of FIG. **7K1**, in accordance with various examples. FIG. **7K3** is a perspective view of the structure of FIG. **7K1**, in accordance with various examples.

[0033] The method **600** also includes applying a mold compound to the device side of the semiconductor die and to an exterior surface of the metal ring facing away from the sensor, where the mold compound is absent from the cavity (**612**). FIG. **7L1** is a profile, cross-sectional view of the structure of FIG. **7K1**, but with the application of the mold compound **138**. The mold compound **138** may be applied, for example, in a mold chase, such as by mold injection techniques. A component of the mold chase may cover the entrance to the cavity **113**, and because no orifices to the cavity **113** exist in the semiconductor die **102**, metal ring **112**, solder **116**, or tie bar ring **126**, no mold compound can enter the cavity **113**. Consequently, no mold compound covers the sensor **110**, which is a desirable result. Because the metal ring **112** does not have a mushroom shape, and further because the sensor semiconductor package **100** lacks wire bonds and/or bond wires, the technical requirement to ensure mushroom metal ring height is at least as tall as bond wire height is mitigated, allowing for thinner, lighter, and less expensive sensor semiconductor packages **100**. Further, specially-designed mold chases, mold assists, and other such approaches are rendered unnecessary, thus significantly reducing manufacturing time, complexity, and expense. FIG. **7L2** is a top-down view of the structure of FIG. **7L1**, in accordance with various examples. FIG. **7L3** is a perspective view of the structure of FIG. **7L1**, in accordance with various examples. FIG. **7M1** is a profile, cross-sectional view of the structure of FIG. **7L1**, except that the structure has been rotated by **180** degrees to depict the structure in an upright orientation. FIG. **7M2** is a top-down view of the structure of FIG. **7M1**, in accordance with various examples. FIG. **7M3** is a perspective view of the structure of FIG. **7M1**, in accordance with various examples.

[0034] The sensor semiconductor package **100** may be incorporated into a variety of devices and in a variety of applications. For example, FIG. **8** is a block diagram of an electronic device **800**. The electronic device **800** may be, or may be included in, smartphones, notebooks, tablets, laptop computers, desktop computers, servers, home or commercial appliances, automobiles, aircraft, watercraft, spacecraft, etc. The electronic device **800** may include a printed circuit board (PCB) **802**. The PCB **802** may have coupled thereto circuitry **804** to perform any of a variety of functions, as well as the sensor semiconductor package **100**, which performs any suitable sensing operation. The circuitry **804** may be coupled to the sensor semiconductor package **100**.

[0035] In this description, the term “couple” may cover connections, communications, or signal paths that enable a functional relationship consistent with this description. For example, if device A generates a signal to control device B to perform an action: (a) in a first example, device A is coupled to device B by direct connection; or (b) in a second example, device A is coupled to device B through intervening component C if intervening component C does not alter the functional relationship between device A and device B, such that device B is controlled by device A via the control signal generated by device A.

[0036] In this description, unless otherwise stated, “about,” “approximately” or “substantially”

preceding a parameter means being within ± 10 percent of that parameter. Modifications are possible in the described examples, and other examples are possible within the scope of the claims.

Claims

1. A semiconductor package, comprising: a semiconductor die having a device side including circuitry; a sensor on the device side; a metal ring on the device side to at least partially define a cavity vertically aligned with the sensor, the metal ring having a top metal ring surface facing away from the semiconductor die and an exterior metal ring surface facing away from the sensor; a metal pillar on the device side and having a top metal pillar surface facing away from the semiconductor die; a tie bar extending approximately parallel to the device side of the semiconductor die and coupled with solder to the top metal ring surface, the tie bar exposed to a first exterior surface of the package; a conductive member including a conductive terminal exposed to a second exterior surface of the package, a vertical member coupled to the conductive terminal and extending toward the first exterior surface of the package, and a horizontal member coupled to the vertical member, the horizontal member soldered to the top metal pillar surface; and a mold compound contacting the exterior metal ring surface, the mold compound absent from the cavity.
2. The package of claim 1, wherein the tie bar has a first component and a second component, the second component thicker than the first component.
3. The package of claim 2, wherein the second component is soldered to the top metal ring surface.
4. The package of claim 1, wherein the sensor is a humidity sensor, a salinity sensor, and a pH sensor.
5. The package of claim 1, wherein the metal ring has a uniform thickness throughout a height of the metal ring.
6. The package of claim 1, wherein the mold compound does not cover a top surface of the tie bar, the top surface of the tie bar facing away from the semiconductor die.
7. The package of claim 1, further comprising: a copper layer between the metal pillar and the semiconductor die, the copper layer having a thickness ranging between 4 microns and 25 microns; and a back end of line (BEOL) metal layer in the device side and coupled to the copper layer by vias having diameters ranging between 0.5 microns and 10 microns, the BEOL metal layer having a thickness ranging between 0.2 microns and 3 microns.
8. The package of claim 1, wherein the mold compound contacts an exterior surface of the vertical member facing away from the semiconductor die and a top surface of the conductive terminal facing the first exterior surface of the package.
9. The package of claim 1, wherein the package lacks wire bonds.
10. A semiconductor device, comprising: a semiconductor die having a device side including circuitry and a sensor formed therein and a non-device side opposing the device side; a metal pillar coupled to and extending from the device side; a metal ring coupled to and extending from the device side, the metal ring defining a cavity that is vertically aligned with the sensor; a mold compound having a top surface closer to the device side than the non-device side and covering the semiconductor die, the metal pillar, and an external surface of the metal ring, the mold compound absent from the cavity; a tie bar extending across and exposed to the top surface of the mold compound and including a tie bar ring coupled to the metal ring, the tie bar ring thicker than a remainder of the tie bar; and a conductive member coupled to the metal pillar and extending to a bottom surface of the mold compound opposite the top surface of the mold compound, an entirety of the conductive member located farther from the top surface of the mold compound than the tie bar.
11. The device of claim 10, further comprising a printed circuit board (PCB) to which the semiconductor device is coupled and second circuitry coupled to the PCB.
12. The device of claim 10, wherein the metal ring is coupled to the tie bar ring using a solder

composed of tin in the range of 80% to 100%, silver in the range of 1% to 5%, and copper in the range of 0% to 5%.

13. The device of claim 10, wherein the device lacks bond wires.

14. The device of claim 10, wherein the sensor is one of a humidity sensor, a salinity sensor, and a pH sensor.

15. The device of claim 10, wherein the metal ring has a uniform thickness throughout a height of the metal ring.

16. The device of claim 10, wherein the metal ring is coupled to the tie bar ring using a solder composed of either bismuth-indium solder or a bismuth-tin alloy.

17. A method for manufacturing a package, comprising: plating a metal ring on a device side of a semiconductor die to at least partially define a cavity, the device side including circuitry and a sensor; plating a metal pillar on the device side of the semiconductor die; depositing solder on a top surface of the metal ring opposite the semiconductor die and on a top surface of the metal pillar; using the solder on the top surface of the metal ring to couple the metal ring to a tie bar extending approximately parallel to the semiconductor die; using the solder on the top surface of the metal pillar to couple the metal pillar to a conductive member having a horizontal member extending approximately parallel to the semiconductor die, a vertical member extending away from the horizontal member, and a conductive terminal extending horizontally away from the semiconductor die; and applying a mold compound to the device side of the semiconductor die and to an exterior surface of the metal ring facing away from the sensor, the mold compound absent from the cavity.

18. The method of claim 17, wherein the metal ring has an approximately uniform thickness throughout a height of the metal ring.

19. The method of claim 17, wherein the tie bar is exposed to multiple surfaces of the package.

20. The method of claim 19, wherein the tie bar includes a first component exposed to a top surface of the mold compound, the tie bar including a second component thicker than the first component and exposed to the top surface of the mold compound, the second component having a ring shape.

21. The method of claim 17, wherein the package omits wire bonds.

22. The method of claim 17, wherein the metal pillar has a thickness ranging from 10 microns to 80 microns.

23. The method of claim 22, wherein a copper layer is on the device side between the metal pillar and the circuitry, and wherein the copper layer is in vertical alignment with the metal pillar and the circuitry, the copper layer having a thickness ranging between 4 microns and 25 microns.
