

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401113
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Jeon; Seunggil et al.

Antenna and electronic device including the same

Abstract

An electronic device is provided. The electronic device includes a front cover, a rear cover, an array antenna, and a support member. The support member includes a conductive first portion forming a lateral appearance of the electronic device, a second portion adjacent to the array antenna, the front cover, and the conductive first portion, and having at least one opening filled with a non-conductive material, and a third portion including a non-conductive material and disposed adjacent to the array antenna, the rear cover, and the conductive first portion. The conductive first portion is exposed to an outside of the electronic device, and the second and third portions are hidden by the front and rear covers. A beam formed by the array antenna is radiated to the outside through the at least one opening and the third portion.

Inventors: Jeon; Seunggil (Suwon-si, KR), Kim; Namwoo (Suwon-si, KR), Hong; Seongbeom (Suwon-si, KR), Moon; Kyunghoon (Suwon-si, KR), Lee; Yunbum (Suwon-si, KR)

Applicant: Samsung Electronics Co., Ltd. (Suwon-si, KR)

Family ID: 1000008778673

Assignee: Samsung Electronics Co., Ltd. (Suwon-si, KR)

Appl. No.: 18/470038

Filed: September 19, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240014544 A1	Jan. 11, 2024

Foreign Application Priority Data

KR	10-2019-0056592	May. 14, 2019
KR	10-2020-0031173	Mar. 13, 2020

Related U.S. Application Data

continuation parent-doc US 16866011 20200504 US 11777193 child-doc US 18470038

Publication Classification

Int. Cl.: **H01Q1/22** (20060101); **H01Q1/24** (20060101); **H01Q21/06** (20060101); **H04M1/02** (20060101)

U.S. Cl.:

CPC **H01Q1/243** (20130101); **H01Q21/065** (20130101); **H04M1/0266** (20130101); **H04M1/0277** (20130101);

Field of Classification Search

CPC: H01Q (1/243); H01Q (21/065); H01Q (1/12); H01Q (1/42); H01Q (9/0407); H01Q (21/08); H01Q (1/22); H01Q (1/241); H04M (1/0266); H04M (1/0277); H04M (1/026)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
11264734	12/2021	Lee et al.	N/A	N/A
2004/0051670	12/2003	Sato	N/A	N/A
2009/0174612	12/2008	Ayala et al.	N/A	N/A
2009/0262029	12/2008	Chiang et al.	N/A	N/A
2012/0034954	12/2011	Tabe	N/A	N/A
2013/0027892	12/2012	Lim	361/679.01	H04M 1/185
2014/0232607	12/2013	Lee	343/841	H04B 15/04
2015/0155614	12/2014	Youn	343/702	H04M 1/0202
2016/0351996	12/2015	Ou	N/A	N/A
2016/0351998	12/2015	Ahn et al.	N/A	N/A
2017/0133748	12/2016	Kim	N/A	H01Q 9/42
2017/0135239	12/2016	Hyun et al.	N/A	N/A
2017/0207516	12/2016	Koo et al.	N/A	N/A
2017/0263998	12/2016	Park et al.	N/A	N/A
2017/0365911	12/2016	Zachara et al.	N/A	N/A
2018/0241115	12/2017	Cho	N/A	H01Q 1/36
2018/0269561	12/2017	Kim et al.	N/A	N/A
2018/0277929	12/2017	Seo et al.	N/A	N/A
2018/0331418	12/2017	Kim	N/A	H01Q 1/243
2018/0366813	12/2017	Kim et al.	N/A	N/A

2019/0027807	12/2018	Choi	N/A	H01Q 5/378
2019/0104212	12/2018	Lee et al.	N/A	N/A
2019/0115648	12/2018	Subba et al.	N/A	N/A
2019/0121396	12/2018	Ha et al.	N/A	N/A
2019/0132973	12/2018	Lee	N/A	G06F 1/1637
2019/0165470	12/2018	Jeon	N/A	N/A
2019/0165473	12/2018	Yun et al.	N/A	N/A
2019/0257933	12/2018	Nath et al.	N/A	N/A
2019/0267718	12/2018	Rajagopalan et al.	N/A	N/A
2019/0305405	12/2018	Im et al.	N/A	N/A
2020/0153115	12/2019	Yun	N/A	H01Q 1/2283
2020/0203804	12/2019	Khripkov	N/A	H01Q 1/243
2020/0259251	12/2019	Seo	N/A	H01Q 21/061
2020/0266521	12/2019	Jeong et al.	N/A	N/A
2020/0266522	12/2019	Moon	N/A	H04M 1/026
2020/0358203	12/2019	Park	N/A	H01Q 1/243
2020/0365972	12/2019	Jeon	N/A	H01Q 21/08
2021/0218128	12/2020	Lee	N/A	H01Q 21/062
2021/0280971	12/2020	Kim	N/A	H01Q 1/243
2021/0328362	12/2020	Park	N/A	H01Q 19/06
2022/0094067	12/2021	Rupakula	N/A	H01Q 1/40
2022/0102869	12/2021	Park	N/A	H01Q 1/243

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101911379	12/2009	CN	N/A
108631039	12/2017	CN	N/A
108633199	12/2017	CN	N/A
111564691	12/2019	CN	N/A
2 110 882	12/2008	EP	N/A
3 098 902	12/2015	EP	N/A
3 696 912	12/2019	EP	N/A
10-2020-0099813	12/2019	KR	N/A
2 265 264	12/2004	RU	N/A

OTHER PUBLICATIONS

Brazilian Notice of Allowance dated Sep. 18, 2023, issued in Brazilian application No. 12 2022 007185 6. cited by applicant
Russian Office Action dated Oct. 17, 2023, issued in Russian Patent Application No. 021132953. cited by applicant
International Search Report with Written Opinion dated Aug. 13, 2020; International Appln. No. PCT/KR2020/005858. cited by applicant
U.S. Notice of Allowance dated Jul. 14, 2020; U.S. Appl. No. 16/884,713. cited by applicant
European Search Report dated Mar. 16, 2021; European Appln. No. 20729607.0-1205 / 3756240 PCT/KR2020005858. cited by applicant
Australian Office Action dated Mar. 22, 2021; Australian Appln. No. 2020204043. cited by applicant
Chinese Office Action with English translation dated Nov. 26, 2021; Chinese Appln. No. 202080003642.0. cited by applicant
Brazilian Notice of Allowance dated Oct. 25, 2022, issued in Brazilian application No. 11 2021 022807 1. cited by applicant
Chinese Office Action dated Nov. 10, 2022, issued in Chinese Application No. 202080003642.0. cited by applicant
Korean Notice of Allowance dated Jan. 2, 2024, issued in Korean Patent Application No. 10-2020-0031173. cited by applicant
Russian Decision on Grant dated Jan. 23, 2024, issued in Russian Patent Application No. 2021132953. cited by applicant
Korean Notice of Allowance dated Sep. 2, 2024, issued in Korean Patent Application No. 10-2020-0062158. cited by applicant
Malaysian Office Action dated Dec. 2, 2024; Malaysian Appln. No. PI2021006652. cited by applicant

Primary Examiner: Lopez Cruz; Dimary S

Assistant Examiner: Immanuel; Bamidele A

Attorney, Agent or Firm: Jefferson IP Law, LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION(S) (1) This application is a continuation application of prior application Ser. No. 16/866,011, filed on May 4, 2020, which claimed priority under 35 U.S.C. 119(a) of a Korean patent application number 10-2019-0056592 filed on May 14, 2019, in the Korean Intellectual Property Office, and of a Korean patent application number 10-2020-0031173, filed on Mar. 13, 2020, in the Korean Intellectual Property Office, the disclosures of each of which are incorporated by reference herein in their entireties.

BACKGROUND

1. Field

(1) The disclosure relates to an antenna and an electronic device including the same.

2. Description of Related Art

(2) With the development of wireless communication technology, electronic devices (e.g., communication electronic devices) are commonly used in daily life; thus, use of content is increasing exponentially. Because of such rapid increase in the use of content, a network capacity is reaching its limit. After commercialization of 4th generation (4G) communication systems, in order

to meet growing wireless data traffic demand, a communication system (e.g., 5th generation (5G) or pre-5G communication system, or new radio (NR))) that transmits and/or receives signals using a frequency of a high frequency (e.g., millimeter wave (mmWave)) band (e.g., 3 GHz to 300 GHz band) is being studied.

(3) Next-generation wireless communication technologies are currently developed to permit signal transmission/reception using frequencies in the range of 3 GHz to 100 GHz, overcome a high free space loss due to frequency characteristics, implement an efficient mounting structure for increasing an antenna gain, and realize a related new antenna module. This antenna module may include an array-type antenna module in which various numbers of antenna elements (e.g., conductive patches) are arranged at regular intervals. These antenna elements may be disposed in an electronic device so as to form a beam pattern in one direction, for example, toward a front, rear, or lateral surface of the electronic device from an inner space of the electronic device.

(4) The electronic device may include a conductive portion (e.g., a metal member) disposed on at least a part of a housing to reinforce the rigidity and create a beautiful appearance, and a non-conductive portion (e.g., a polymer member) combined with the conductive portion. However, when the conductive portion is placed near the antenna module disposed inside the electronic device, the radiation performance and radiation sensitivity of the antenna module may be deteriorated.

(5) The non-conductive portion may be insert-injected into or structurally combined with the conductive portion to form a single housing. Further, in order to prevent the conductive portion and the non-conductive portion from being separated by an external impact, a boundary region between the conductive portion and the non-conductive portion may have an engaging structure composed of at least one protrusion and at least one recess for receiving the at least one protrusion. A portion of the housing faced by the antenna module that forms a beam pattern in a specific direction from the inner space of the electronic device may be formed as the non-conductive portion. Thus, the boundary region between the conductive portion and the non-conductive portion may be placed near the antenna module, and a concave part of the conductive portion produced by the engaging structure composed of the protrusion and the recess may also be placed near the antenna module.

(6) Unfortunately, this concave part may cause an excitation current, so that the antenna module may be confronted with the degradation of radiation performance and radiation sensitivity.

(7) The above information is presented as background information only, and to assist with an understanding of the disclosure. No determination has been made, and no assertion is made, as to whether any of the above might be applicable as prior art with regard to the disclosure.

SUMMARY

(8) Aspects of the disclosure are to address at least the above-mentioned problems and/or disadvantages and to provide at least the advantages described below. Accordingly, an aspect of the disclosure is to provide an apparatus and method for an antenna and an electronic device including the same.

(9) Another aspect of the disclosure is to provide an apparatus and method for an electronic device capable of preventing the degradation of antenna radiation performance through a structural modification of a housing.

(10) Another aspect of the disclosure is to provide an apparatus and method for an electronic device capable of preventing the damage of a housing due to an external impact and also preventing the degradation of antenna performance.

(11) Additional aspects will be set forth in part in the description which follows and, in part, will be apparent from the description, or may be learned by practice of the presented embodiments.

(12) In accordance with an aspect of the disclosure, an electronic device is provided. The electronic device includes a front cover, a rear cover, an array antenna, and a support member. The front cover and the rear cover form a part of an outer appearance of the electronic device. The array antenna includes a plurality of antenna elements disposed between the front cover and the rear cover. The

support member is disposed between the front cover and the rear cover, and is configured to support a display of the electronic device and extend to a lateral surface of the electronic device to form at least in part a lateral appearance of the electronic device. The support member includes a conductive first portion forming the lateral appearance of the electronic device, a second portion adjacent to the array antenna, the front cover, and the conductive first portion, and having at least one opening filled with a non-conductive material, and a third portion formed of a non-conductive material and adjacent to the array antenna, the rear cover, and the conductive first portion. The first portion is exposed to an outside of the electronic device, and the second and third portions are hidden by the front and rear covers so as not to be exposed to the outside. A beam formed by the array antenna is radiated to the outside through the at least one opening and the third portion.

(13) In accordance with another aspect of the disclosure, a portable communication device is provided. The portable communication device includes a housing, a display, and an antenna module. The housing includes a first member forming a front portion of the portable communication device, a second member forming a rear portion of the portable communication device, and a third member forming a lateral portion of the portable communication device. The third member includes a conductive member having an opening formed therein, and a non-conductive member filled in the opening. One surface of the conductive member is exposed to an outside of the portable communication device, and the non-conductive member is disposed in the housing so as not to be exposed to the outside. The display is disposed under the first member and visually seen to the outside through the first member. The antenna module is disposed between the display and the second member and include an antenna and a printed circuit board. The antenna is formed on the printed circuit board such that a signal radiated from the antenna is transmitted to the outside through the non-conductive member.

(14) Other aspects, advantages, and salient features of the disclosure will become apparent to those skilled in the art from the following detailed description, which, taken in conjunction with the annexed drawings, discloses various embodiments of the disclosure.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) The above and other aspects, features and advantages of certain embodiments of the disclosure will be more apparent from the following description, taken in conjunction with the accompanying drawings, in which:
- (2) FIG. 1 is a block diagram illustrating an electronic device in a network environment according to an embodiment of the disclosure.
- (3) FIG. 2 is a block diagram illustrating an electronic device for supporting a legacy network communication and a 5G network communication according to an embodiment of the disclosure.
- (4) FIG. 3A is a perspective view showing a front surface of a mobile electronic device according to an embodiment of the disclosure.
- (5) FIG. 3B is a perspective view showing a rear surface of the mobile electronic device shown in FIG. 3A according to an embodiment of the disclosure.
- (6) FIG. 3C is an exploded perspective view showing the mobile electronic device shown in FIGS. 3A and 3B according to an embodiment of the disclosure.
- (7) FIG. 4A shows an embodiment of a structure of the third antenna module shown in and described with reference to FIG. 2 according to an embodiment of the disclosure.
- (8) FIG. 4B is a cross-sectional view taken along line Y-Y' in FIG. 4A according to an embodiment of the disclosure.
- (9) FIG. 5 is a perspective view showing an antenna module according to an embodiment of the disclosure.

- (10) FIG. 6A is an exploded perspective view showing an antenna module and a conductive member to be applied thereto according to an embodiment of the disclosure.
- (11) FIG. 6B is a perspective view showing an antenna module and a conductive member applied thereto according to an embodiment of the disclosure.
- (12) FIG. 7 is a cross-sectional view partially showing an electronic device, viewed from line A-A' in FIG. 3B, according to an embodiment of the disclosure.
- (13) FIG. 8A is a view partially showing an electronic device, viewed from line B-B' in FIG. 3B, according to an embodiment of the disclosure.
- (14) FIG. 8B is a view partially showing a lateral member having a non-conductive region around an antenna module according to an embodiment of the disclosure.
- (15) FIGS. 9A and 9B are graphs showing radiation patterns and gains by horizontal polarization of an antenna module according to various embodiments of the disclosure.
- (16) FIG. 9C is a graph showing a radiation pattern by vertical polarization of an antenna module according to an embodiment of the disclosure.
- (17) FIG. 10 is a cross-sectional view partially showing an electronic device, viewed from line C-C' in FIG. 3A, according to an embodiment of the disclosure.
- (18) FIG. 11A is a perspective view partially showing a housing according to an embodiment of the disclosure.
- (19) FIG. 11B is a perspective view partially showing a housing according to an embodiment of the disclosure.
- (20) FIGS. 12A and 12B are graphs showing radiation patterns and gains by horizontal polarization of the antenna module of FIG. 10 according to various embodiments of the disclosure.
- (21) FIG. 13 is a cross-sectional view partially showing an electronic device including a conductive connection member according to an embodiment of the disclosure.
- (22) FIG. 14A is a radiation pattern view showing horizontal polarization of an antenna module before and after a movement of a conductive connection member according to an embodiment of the disclosure.
- (23) FIG. 14B is a radiation pattern view showing vertical polarization of an antenna module before and after a movement of a conductive connection member according to an embodiment of the disclosure.
- (24) FIG. 15 is a perspective view partially showing an electronic device including a conductive sheet having a notch according to an embodiment of the disclosure.
- (25) FIG. 16 is a graph showing radiation patterns by vertical polarization and horizontal polarization of an antenna module disposed in the electronic device of FIG. according to an embodiment of the disclosure.
- (26) FIG. 17 is a cross-sectional view partially showing an electronic device according to an embodiment of the disclosure.
- (27) FIG. 18 is a cross-sectional view partially showing an electronic device according to an embodiment of the disclosure.
- (28) FIGS. 19A and 19B are perspective views partially showing a support member according to various embodiments of the disclosure.
- (29) FIGS. 20A and 20B are perspective views partially showing an electronic device including a conductive sheet having a slot according to various embodiments of the disclosure.
- (30) Throughout the drawings, like reference numerals will be understood to refer to like parts, components, and structures.

DETAILED DESCRIPTION

(31) The following description with reference to accompanying drawings is provided to assist in a comprehensive understanding of various embodiments of the disclosure as defined by the claims and their equivalents. It includes various specific details to assist in that understanding but these are to be regarded as merely exemplary. Accordingly, those of ordinary skill in the art will recognize

that various changes and modifications of the various embodiments described herein can be made without departing from the scope and spirit of the disclosure. In addition, descriptions of well-known functions and constructions may be omitted for clarity and conciseness.

(32) The terms and words used in the following description and claims are not limited to the bibliographical meanings, but are merely used to enable a clear and consistent understanding of the disclosure. Accordingly, it should be apparent to those skilled in the art that the following description of various embodiments of the disclosure is provided for illustration purpose only and not for the purpose of limiting the disclosure as defined by the appended claims and their equivalents.

(33) It is to be understood that the singular forms “a,” “an,” and “the” include plural referents unless the context clearly dictates otherwise. Thus, for example, reference to “a component surface” includes reference to one or more of such surfaces. FIG. 1 illustrates an electronic device in a network environment according to an embodiment of the disclosure.

(34) Referring to FIG. 1, an electronic device **101** in a network environment **100** may communicate with an electronic device **102** via a first network **198** (e.g., a short-range wireless communication network), or an electronic device **104** or a server **108** via a second network **199** (e.g., a long-range wireless communication network). The electronic device **101** may communicate with the electronic device **104** via the server **108**. The electronic device **101** includes a processor **120**, memory **130**, an input device **150**, an audio output device **155**, a display device **160**, an audio module **170**, a sensor module **176**, an interface **177**, a haptic module **179**, a camera module **180**, a power management module **188**, a battery **189**, a communication module **190**, a subscriber identification module (SIM) **196**, and/or an antenna module **197**. In some embodiments, at least one (e.g., the display device **160** or the camera module **180**) of the components may be omitted from the electronic device **101**, or one or more other components may be added in the electronic device **101**. In some embodiments, some of the components may be implemented as single integrated circuitry. For example, the sensor module **176** (e.g., a fingerprint sensor, an iris sensor, or an illuminance sensor) may be implemented as embedded in the display device **160** (e.g., a display).

(35) The processor **120** may execute, for example, software (e.g., a program **140**) to control at least one other component (e.g., a hardware or software component) of the electronic device **101** coupled with the processor **120**, and may perform various data processing or computation. As at least part of the data processing or computation, the processor **120** may load a command or data received from another component (e.g., the sensor module **176** or the communication module **190**) in volatile memory **132**, process the command or the data stored in the volatile memory **132**, and store resulting data in non-volatile memory **134**. The processor **120** may include a main processor **121** (e.g., a central processing unit (CPU) or an application processor (AP)), and an auxiliary processor **123** (e.g., a graphics processing unit (GPU), an image signal processor (ISP), a sensor hub processor, or a communication processor (CP)) that is operable independently from, or in conjunction with, the main processor **121**. Additionally or alternatively, the auxiliary processor **123** may be adapted to consume less power than the main processor **121**, or to be specific to a specified function. The auxiliary processor **123** may be implemented as separate from, or as part of the main processor **121**.

(36) The auxiliary processor **123** may control at least some of functions or states related to at least one component (e.g., the display device **160**, the sensor module **176**, or the communication module **190**) among the components of the electronic device **101**, instead of the main processor **121** while the main processor **121** is in an inactive (e.g., sleep) state, or together with the main processor **121** while the main processor **121** is in an active state (e.g., executing an application). The auxiliary processor **123** (e.g., an ISP or a CP) may be implemented as part of another component (e.g., the camera module **180** or the communication module **190**) functionally related to the auxiliary processor **123**.

(37) The memory **130** may store various data used by at least one component (e.g., the processor

120 or the sensor module **176**) of the electronic device **101**. The various data may include, for example, software (e.g., the program **140**) and input data or output data for a command related thereto. The memory **130** may include the volatile memory **132** or the non-volatile memory **134**, and the non-volatile memory may include one or more of an internal memory **136** and external memory **138**.

(38) The program **140** may be stored in the memory **130** as software, and may include, for example, an operating system (OS) **142**, middleware **144**, and/or an application **146**.

(39) The input device **150** may receive a command or data to be used by other components (e.g., the processor **120**) of the electronic device **101**, from the outside (e.g., a user) of the electronic device **101**. The input device **150** may include, for example, a microphone, a mouse, a keyboard, or a digital pen (e.g., a stylus pen).

(40) The audio output device **155** may output sound signals to the outside of the electronic device **101**. The audio output device **155** may include, for example, a speaker or a receiver. The speaker may be used for general purposes, such as playing multimedia or playing record, and the receiver may be used for incoming calls. The receiver may be implemented as separate from, or as part of the speaker.

(41) The display device **160** may visually provide information to the outside (e.g., a user) of the electronic device **101**. The display device **160** may include, for example, a display, a hologram device, or a projector and control circuitry to control a corresponding one of the display, hologram device, and projector. The display device **160** may include touch circuitry adapted to detect a touch, or sensor circuitry (e.g., a pressure sensor) adapted to measure the intensity of force incurred by the touch.

(42) The audio module **170** may convert a sound into an electrical signal and vice versa. The audio module **170** may obtain the sound via the input device **150**, or output the sound via the audio output device **155** or a headphone of an external electronic device (e.g., an electronic device **102**) directly (e.g., wiredly) or wirelessly coupled with the electronic device **101**.

(43) The sensor module **176** may detect an operational state (e.g., power or temperature) of the electronic device **101** or an environmental state (e.g., a state of a user) external to the electronic device **101**, and then generate an electrical signal or data value corresponding to the detected state. The sensor module **176** may include, for example, a gesture sensor, a gyro sensor, an atmospheric pressure sensor, a magnetic sensor, an acceleration sensor, a grip sensor, a proximity sensor, a color sensor, an infrared (IR) sensor, a biometric sensor, a temperature sensor, a humidity sensor, or an illuminance sensor.

(44) The interface **177** may support one or more specified protocols to be used for the electronic device **101** to be coupled with the external electronic device (e.g., the electronic device **102**) directly (e.g., wiredly) or wirelessly. The interface **177** may include, for example, a high definition multimedia interface (HDMI), a universal serial bus (USB) interface, a secure digital (SD) card interface, or an audio interface.

(45) A connection terminal **178** may include a connector via which the electronic device **101** may be physically connected with the external electronic device (e.g., the electronic device **102**). The connection terminal **178** may include, for example, a HDMI connector, a USB connector, a SD card connector, or an audio connector (e.g., a headphone connector).

(46) The haptic module **179** may convert an electrical signal into a mechanical stimulus (e.g., a vibration or a movement) or electrical stimulus which may be recognized by a user via his tactile sensation or kinesthetic sensation. The haptic module **179** may include, for example, a motor, a piezoelectric element, or an electric stimulator.

(47) The camera module **180** may capture an image or moving images. The camera module **180** may include one or more lenses, image sensors, image signal processors, or flashes.

(48) The power management module **188** may manage power supplied to the electronic device **101**. The power management module **188** may be implemented as at least part of, for example, a power

management integrated circuit (PMIC).

(49) The battery **189** may supply power to at least one component of the electronic device **101**. The battery **189** may include, for example, a primary cell which is not rechargeable, a secondary cell which is rechargeable, or a fuel cell.

(50) The communication module **190** may support establishing a direct (e.g., wired) communication channel or a wireless communication channel between the electronic device **101** and the external electronic device (e.g., the electronic device **102**, the electronic device **104**, or the server **108**) and performing communication via the established communication channel. The communication module **190** may include one or more communication processors that are operable independently from the processor **120** (e.g., the AP) and supports a direct (e.g., wired) communication or a wireless communication. The communication module **190** may include a wireless communication module **192** (e.g., a cellular communication module, a short-range wireless communication module, or a global navigation satellite system (GNSS) communication module) or a wired communication module **194** (e.g., a local area network (LAN) communication module or a power line communication (PLC) module). A corresponding one of these communication modules may communicate with the external electronic device via the first network **198** (e.g., a short-range communication network, such as Bluetooth™, wireless-fidelity (Wi-Fi) direct, or infrared data association (IrDA)) or the second network **199** (e.g., a long-range communication network, such as a cellular network, the Internet, or a computer network (e.g., LAN or wide area network (WAN))). These various types of communication modules may be implemented as a single component (e.g., a single chip), or may be implemented as multi components (e.g., multi chips) separate from each other. The wireless communication module **192** may identify and authenticate the electronic device **101** in a communication network, such as the first network **198** or the second network **199**, using subscriber information (e.g., international mobile subscriber identity (IMSI)) stored in the SIM **196**.

(51) The antenna module **197** may transmit or receive a signal or power to or from the outside (e.g., the external electronic device) of the electronic device **101**. The antenna module **197** may include an antenna including a radiating element composed of a conductive material or a conductive pattern formed in or on a substrate (e.g., a printed circuit board (PCB)). The antenna module **197** may include a plurality of antennas. In such a case, at least one antenna appropriate for a communication scheme used in the communication network, such as the first network **198** or the second network **199**, may be selected, for example, by the communication module **190** (e.g., the wireless communication module **192**) from the plurality of antennas. The signal or the power may then be transmitted or received between the communication module **190** and the external electronic device via the selected at least one antenna. Another component (e.g., a radio frequency integrated circuit (RFIC)) other than the radiating element may be additionally formed as part of the antenna module **197**.

(52) At least some of the above-described components may be coupled mutually and communicate signals (e.g., commands or data) therebetween via an inter-peripheral communication scheme (e.g., a bus, general purpose input and output (GPIO), serial peripheral interface (SPI), or mobile industry processor interface (MIPI)).

(53) Commands or data may be transmitted or received between the electronic device **101** and the external electronic device **104** via the server **108** coupled with the second network **199**. Each of the electronic devices **102** and **104** may be a device of a same type as, or a different type, from the electronic device **101**. All or some of operations to be executed at the electronic device **101** may be executed at one or more of the external electronic devices **102**, **104**, or **108**. For example, if the electronic device **101** should perform a function or a service automatically, or in response to a request from a user or another device, the electronic device **101**, instead of, or in addition to, executing the function or the service, may request the one or more external electronic devices to perform at least part of the function or the service. The one or more external electronic devices

receiving the request may perform the at least part of the function or the service requested, or an additional function or an additional service related to the request, and transfer an outcome of the performing to the electronic device **101**. The electronic device **101** may provide the outcome, with or without further processing of the outcome, as at least part of a reply to the request. To that end, a cloud computing, distributed computing, or client-server computing technology may be used, for example.

(54) An electronic device according to an embodiment may be one of various types of electronic devices. The electronic device may include a portable communication device (e.g., a smart phone), a computer device, a portable multimedia device, a portable medical device, a camera, a wearable device, or a home appliance. However, the electronic device is not limited to any of those described above.

(55) Various embodiments of the disclosure and the terms used herein are not intended to limit the technological features set forth herein to particular embodiments and include various changes, equivalents, or replacements for a corresponding embodiment.

(56) With regard to the description of the drawings, similar reference numerals may be used to refer to similar or related elements.

(57) A singular form of a noun corresponding to an item may include one or more of the things, unless the relevant context clearly indicates otherwise. As used herein, each of such phrases as “A or B,” “at least one of A and B,” “at least one of A or B,” “A, B, or C,” “at least one of A, B, and C,” and “at least one of A, B, or C” may include any one of, or all possible combinations of the items enumerated together in a corresponding one of the phrases.

(58) As used herein, such terms as “1st” and “2.sup.nd,” or “first” and “second” may be used to simply distinguish a corresponding component from another, and does not limit the components in other aspect (e.g., importance or order). If an element (e.g., a first element) is referred to, with or without the term “operatively” or “communicatively,” as “coupled with,” “coupled to,” “connected with,” or “connected to” another element (e.g., a second element), it means that the element may be coupled with the other element directly (e.g., wiredly), wirelessly, or via a third element.

(59) The term “module” may include a unit implemented in hardware, software, or firmware, and may interchangeably be used with other terms, for example, “logic,” “logic block,” “part,” or “circuitry.” A module may be a single integral component, or a minimum unit or part thereof, adapted to perform one or more functions. For example, according to an embodiment, the module may be implemented in a form of an application-specific integrated circuit (ASIC).

(60) Various embodiments as set forth herein may be implemented as software (e.g., the program **140**) including one or more instructions that are stored in a storage medium (e.g., the internal memory **136** or external memory **138**) that is readable by a machine (e.g., the electronic device **101**). For example, a processor (e.g., the processor **120**) of the machine (e.g., the electronic device **101**) may invoke at least one of the one or more instructions stored in the storage medium, and execute it, with or without using one or more other components under the control of the processor. This allows the machine to be operated to perform at least one function according to the at least one instruction invoked. The one or more instructions may include a code generated by a compiler or a code executable by an interpreter. The machine-readable storage medium may be provided in the form of a non-transitory storage medium. Wherein, the term “non-transitory” simply means that the storage medium is a tangible device, and does not include a signal (e.g., an electromagnetic wave), but this term does not differentiate between where data is semi-permanently stored in the storage medium and where the data is temporarily stored in the storage medium.

(61) A method according to an embodiment of the disclosure may be included and provided in a computer program product. The computer program product may be traded as a product between a seller and a buyer. The computer program product may be distributed in the form of a machine-readable storage medium (e.g., compact disc read only memory (CD-ROM)), or be distributed (e.g., downloaded or uploaded) online via an application store (e.g., PlayStore™), or between two

user devices (e.g., smart phones) directly. If distributed online, at least part of the computer program product may be temporarily generated or at least temporarily stored in the machine-readable storage medium, such as memory of the manufacturer's server, a server of the application store, or a relay server.

(62) Each component (e.g., a module or a program) of the above-described components may include a single entity or multiple entities. One or more of the above-described components may be omitted, or one or more other components may be added. Alternatively or additionally, a plurality of components (e.g., modules or programs) may be integrated into a single component. In such a case, the integrated component may perform one or more functions of each of the plurality of components in the same or similar manner as they are performed by a corresponding one of the plurality of components before the integration. Operations performed by the module, the program, or another component may be carried out sequentially, in parallel, repeatedly, or heuristically, or one or more of the operations may be executed in a different order or omitted, or one or more other operations may be added.

(63) FIG. 2 is a block diagram illustrating an electronic device in a network environment including a plurality of cellular networks according to an embodiment of the disclosure.

(64) Referring to FIG. 2, the electronic device **101** of block diagram **200** may include a first communication processor **212**, second communication processor **214**, first RFIC **222**, second RFIC **224**, third RFIC **226**, fourth RFIC **228**, first radio frequency front end (RFFE) **232**, second RFFE **234**, first antenna module **242**, second antenna module **244**, and antenna **248**. The electronic device **101** may include the processor **120** and the memory **130**. A second network **199** may include a first cellular network **292** and a second cellular network **294**. According to another embodiment, the electronic device **101** may further include at least one of the components described with reference to FIG. 1, and the second network **199** may further include at least one other network. According to one embodiment, the first communication processor **212**, second communication processor **214**, first RFIC **222**, second RFIC **224**, fourth RFIC **228**, first RFFE **232**, and second RFFE **234** may form at least part of the wireless communication module **192**. According to another embodiment, the fourth RFIC **228** may be omitted or included as part of the third RFIC **226**.

(65) The first communication processor **212** may establish a communication channel of a band to be used for wireless communication with the first cellular network **292** and support legacy network communication through the established communication channel. According to various embodiments, the first cellular network may be a legacy network including a second generation (2G), 3G, 4G, or long-term evolution (LTE) network. The second communication processor **214** may establish a communication channel corresponding to a designated band (e.g., about 6 GHz to about GHz) of bands to be used for wireless communication with the second cellular network **294**, and support 5G network communication through the established communication channel.

According to various embodiments, the second cellular network **294** may be a 5G network defined in 3GPP. Additionally, according to an embodiment, the first communication processor **212** or the second communication processor **214** may establish a communication channel corresponding to another designated band (e.g., about 6 GHz or less) of bands to be used for wireless communication with the second cellular network **294** and support 5G network communication through the established communication channel. According to one embodiment, the first communication processor **212** and the second communication processor **214** may be implemented in a single chip or a single package. According to various embodiments, the first communication processor **212** or the second communication processor **214** may be formed in a single chip or a single package with the processor **120**, the auxiliary processor **123**, or the communication module **190**.

(66) Upon transmission, the first RFIC **222** may convert a baseband signal generated by the first communication processor **212** to a radio frequency (RF) signal of about 700 MHz to about 3 GHz used in the first cellular network **292** (e.g., legacy network). Upon reception, an RF signal may be obtained from the first cellular network **292** (e.g., legacy network) through an antenna (e.g., the

first antenna module **242**) and be preprocessed through an RFFE (e.g., the first RFFE **232**). The first RFIC **222** may convert the preprocessed RF signal to a baseband signal so as to be processed by the first communication processor **212**.

(67) Upon transmission, the second RFIC **224** may convert a baseband signal generated by the first communication processor **212** or the second communication processor **214** to an RF signal (hereinafter, 5G Sub6 RF signal) of a Sub6 band (e.g., 6 GHz or less) to be used in the second cellular network **294** (e.g., 5G network). Upon reception, a 5G Sub6 RF signal may be obtained from the second cellular network **294** (e.g., 5G network) through an antenna (e.g., the second antenna module **244**) and be pretreated through an RFFE (e.g., the second RFFE **234**). The second RFIC **224** may convert the preprocessed 5G Sub6 RF signal to a baseband signal so as to be processed by a corresponding communication processor of the first communication processor **212** or the second communication processor **214**.

(68) The third RFIC **226** may convert a baseband signal generated by the second communication processor **214** to an RF signal (hereinafter, 5G Above6 RF signal) of a 5G Above6 band (e.g., about 6 GHz to about 60 GHz) to be used in the second cellular network **294** (e.g., 5G network). Upon reception, a 5G Above6 RF signal may be obtained from the second cellular network **294** (e.g., 5G network) through an antenna (e.g., the antenna **248**) and be preprocessed through a third RFFE **236**. The third RFIC **226** may convert the preprocessed 5G Above6 RF signal to a baseband signal so as to be processed by the second communication processor **214**. According to one embodiment, the third RFFE **236** may be formed as part of the third RFIC **226**.

(69) According to an embodiment, the electronic device **101** may include a fourth RFIC **228** separately from the third RFIC **226** or as at least part of the third RFIC **226**. In this case, the fourth RFIC **228** may convert a baseband signal generated by the second communication processor **214** to an RF signal (hereinafter, an intermediate frequency (IF) signal) of an intermediate frequency band (e.g., about 9 GHz to about 11 GHz) and transfer the IF signal to the third RFIC **226**. The third RFIC **226** may convert the IF signal to a 5G Above 6RF signal. Upon reception, the 5G Above 6RF signal may be received from the second cellular network **294** (e.g., a 5G network) through an antenna (e.g., the antenna **248**) and be converted to an IF signal by the third RFIC **226**. The fourth RFIC **228** may convert an IF signal to a baseband signal so as to be processed by the second communication processor **214**.

(70) According to one embodiment, the first RFIC **222** and the second RFIC **224** may be implemented into at least part of a single package or a single chip. According to one embodiment, the first RFFE **232** and the second RFFE **234** may be implemented into at least part of a single package or a single chip. According to one embodiment, at least one of the first antenna module **242** or the second antenna module **244** may be omitted or may be combined with another antenna module to process RF signals of a corresponding plurality of bands.

(71) According to one embodiment, the third RFIC **226** and the antenna **248** may be disposed at the same substrate to form a third antenna module **246**. For example, the wireless communication module **192** or the processor **120** may be disposed at a first substrate (e.g., main PCB). In this case, the third RFIC **226** is disposed in a partial area (e.g., lower surface) of the first substrate and a separate second substrate (e.g., sub PCB), and the antenna **248** is disposed in another partial area (e.g., upper surface) thereof; thus, the third antenna module **246** may be formed. By disposing the third RFIC **226** and the antenna **248** in the same substrate, a length of a transmission line therebetween can be reduced. This may reduce, for example, a loss (e.g., attenuation) of a signal of a high frequency band (e.g., about 6 GHz to about 60 GHz) to be used in 5G network communication by a transmission line. Therefore, the electronic device **101** may improve a quality or speed of communication with the second cellular network **294** (e.g., network).

(72) According to one embodiment, the antenna **248** may be formed in an antenna array including a plurality of antenna elements that may be used for beamforming. In this case, the third RFIC **226** may include a plurality of phase shifters **238** corresponding to a plurality of antenna elements, for

example, as part of the third RFFE **236**. Upon transmission, each of the plurality of phase shifters **238** may convert a phase of a 5G Above6 RF signal to be transmitted to the outside (e.g., a base station of a 5G network) of the electronic device **101** through a corresponding antenna element. Upon reception, each of the plurality of phase shifters **238** may convert a phase of the 5G Above6 RF signal received from the outside to the same phase or substantially the same phase through a corresponding antenna element. This enables transmission or reception through beamforming between the electronic device **101** and the outside.

(73) The second cellular network **294** (e.g., 5G network) may operate (e.g., stand-alone (SA)) independently of the first cellular network **292** (e.g., legacy network) or may be operated (e.g., non-stand alone (NSA)) in connection with the first cellular network **292**. For example, the 5G network may have only an access network (e.g., 5G radio access network (RAN) or a next generation (NG) RAN and have no core network (e.g., next generation core (NGC)). In this case, after accessing to the access network of the 5G network, the electronic device **101** may access to an external network (e.g., Internet) under the control of a core network (e.g., an evolved packed core (EPC)) of the legacy network. Protocol information (e.g., LTE protocol information) for communication with a legacy network or protocol information (e.g., new radio (NR) protocol information) for communication with a 5G network may be stored in the memory **130** to be accessed by other components (e.g., the processor **120**, the first communication processor **212**, or the second communication processor **214**).

(74) FIG. **3A** illustrates a perspective view showing a front surface of a mobile electronic device according to an embodiment of the disclosure.

(75) FIG. **3B** illustrates a perspective view showing a rear surface of the mobile electronic device shown in FIG. **3A** according to an embodiment of the disclosure.

(76) Referring to FIGS. **3A** and **3B**, a mobile electronic device **300** may include a housing **310** that includes a first surface (or front surface) **310A**, a second surface (or rear surface) **310B**, and a lateral surface **310C** that surrounds a space between the first surface **310A** and the second surface **310B**. The housing **310** may refer to a structure that forms a part of the first surface **310A**, the second surface **310B**, and the lateral surface **310C**. The first surface **310A** may be formed of a front plate **302** (e.g., a glass plate or polymer plate coated with a variety of coating layers) at least a part of which is substantially transparent. The second surface **310B** may be formed of a rear plate **311** which is substantially opaque. The rear plate **311** may be formed of, for example, coated or colored glass, ceramic, polymer, metal (e.g., aluminum, stainless steel (STS), or magnesium), or any combination thereof. The lateral surface **310C** may be formed of a lateral bezel structure (or “lateral member”) **318** which is combined with the front plate **302** and the rear plate **311** and includes a metal and/or polymer. The rear plate **311** and the lateral bezel structure **318** may be integrally formed and may be of the same material (e.g., a metallic material such as aluminum).

(77) The front plate **302** may include two first regions **310D** disposed at long edges thereof, respectively, and bent and extended seamlessly from the first surface **310A** toward the rear plate **311**. Similarly, the rear plate **311** may include two second regions **310E** disposed at long edges thereof, respectively, and bent and extended seamlessly from the second surface **310B** toward the front plate **302**. The front plate **302** (or the rear plate **311**) may include only one of the first regions **310D** (or of the second regions **310E**). The first regions **310D** or the second regions **310E** may be omitted in part. When viewed from a lateral side of the mobile electronic device **300**, the lateral bezel structure **318** may have a first thickness (or width) on a lateral side where the first region **310D** or the second region **310E** is not included, and may have a second thickness, being less than the first thickness, on another lateral side where the first region **310D** or the second region **310E** is included.

(78) The mobile electronic device **300** may include at least one of a display **301**, audio modules **303**, **307** and **314**, sensor modules **304** and **319**, camera modules **305**, **312** and **313**, a key input device **317**, a light emitting device, and connector holes **308** and **309**. The mobile electronic device

300 may omit at least one (e.g., the key input device **317** or the light emitting device) of the above components, or may further include other components.

(79) The display **301** may be exposed through a substantial portion of the front plate **302**, for example. At least a part of the display **301** may be exposed through the front plate **302** that forms the first surface **310A** and the first region **310D** of the lateral surface **310C**. Outlines (i.e., edges and corners) of the display **301** may have substantially the same form as those of the front plate **302**. The spacing between the outline of the display **301** and the outline of the front plate **302** may be substantially unchanged in order to enlarge the exposed area of the display **301**.

(80) A recess or opening may be formed in a portion of a display area of the display **301** to accommodate at least one of the audio module **314**, the sensor module **304**, the camera module **305**, and the light emitting device. At least one of the audio module **314**, the sensor module **304**, the camera module **305**, a fingerprint sensor (not shown), and the light emitting element may be disposed on the back of the display area of the display **301**. The display **301** may be combined with, or adjacent to, a touch sensing circuit, a pressure sensor capable of measuring the touch strength (pressure), and/or a digitizer for detecting a stylus pen. At least a part of the sensor modules **304** and **319** and/or at least a part of the key input device **317** may be disposed in the first region **310D** and/or the second region **310E**.

(81) The audio modules **303**, **307** and **314** may correspond to a microphone hole **303** and speaker holes **307** and **314**, respectively. The microphone hole **303** may contain a microphone disposed therein for acquiring external sounds and, in a case, contain a plurality of microphones to sense a sound direction. The speaker holes **307** and **314** may be classified into an external speaker hole **307** and a call receiver hole **314**. The microphone hole **303** and the speaker holes **307** and **314** may be implemented as a single hole, or a speaker (e.g., a piezo speaker) may be provided without the speaker holes **307** and **314**.

(82) The sensor modules **304** and **319** may generate electrical signals or data corresponding to an internal operating state of the mobile electronic device **300** or to an external environmental condition. The sensor modules **304** and **319** may include a first sensor module **304** (e.g., a proximity sensor) and/or a second sensor module (e.g., a fingerprint sensor) disposed on the first surface **310A** of the housing **310**, and/or a third sensor module **319** (e.g., a heart rate monitor (HRM) sensor) and/or a fourth sensor module (e.g., a fingerprint sensor) disposed on the second surface **310B** of the housing **310**. The fingerprint sensor may be disposed on the second surface **310B** as well as the first surface **310A** (e.g., the display **301**) of the housing **310**. The electronic device **300** may further include at least one of a gesture sensor, a gyro sensor, an air pressure sensor, a magnetic sensor, an acceleration sensor, a grip sensor, a color sensor, an infrared (IR) sensor, a biometric sensor, a temperature sensor, a humidity sensor, or an illuminance sensor.

(83) The camera modules **305**, **312** and **313** may include a first camera device **305** disposed on the first surface **310A** of the electronic device **300**, and a second camera module **312** and/or a flash **313** disposed on the second surface **310B**. The camera module **305** or the camera module **312** may include one or more lenses, an image sensor, and/or an image signal processor. The flash **313** may include, for example, a light emitting diode or a xenon lamp. Two or more lenses (infrared cameras, wide angle and telephoto lenses) and image sensors may be disposed on one side of the electronic device **300**.

(84) The key input device **317** may be disposed on the lateral surface **310C** of the housing **310**. The mobile electronic device **300** may not include some or all of the key input device **317** described above, and the key input device **317** which is not included may be implemented in another form such as a soft key on the display **301**. The key input device **317** may include the sensor module disposed on the second surface **310B** of the housing **310**.

(85) The light emitting device may be disposed on the first surface **310A** of the housing **310**. For example, the light emitting device may provide status information of the electronic device **300** in an optical form. The light emitting device may provide a light source associated with the operation

of the camera module **305**. The light emitting device may include, for example, a light emitting diode (LED), an IR LED, or a xenon lamp.

(86) The connector holes **308** and **309** may include a first connector hole **308** adapted for a connector (e.g., a universal serial bus (USB) connector) for transmitting and receiving power and/or data to and from an external electronic device, and/or a second connector hole **309** adapted for a connector (e.g., an earphone jack) for transmitting and receiving an audio signal to and from an external electronic device.

(87) Some modules **305** of camera modules **305** and **312**, some sensor modules **304** of sensor modules **304** and **319**, or an indicator may be arranged to be exposed through a display **301**. For example, the camera module **305**, the sensor module **304**, or the indicator may be arranged in the internal space of an electronic device **300** so as to be brought into contact with an external environment through an opening of the display **301**, which is perforated up to a front plate **302**. In another embodiment, some sensor modules **304** may be arranged to perform their functions without being visually exposed through the front plate **302** in the internal space of the electronic device. For example, in this case, an area of the display **301** facing the sensor module may not require a perforated opening.

(88) FIG. 3C illustrates an exploded perspective view showing a mobile electronic device shown in FIG. 3A according to an embodiment of the disclosure.

(89) Referring to FIG. 3C, the mobile electronic device **300** may include a lateral bezel structure **320**, a first support member **3211** (e.g., a bracket), the front plate **302**, the display **301**, an electromagnetic induction panel (not shown), a printed circuit board (PCB) **340**, a battery **350**, a second support member **360** (e.g., a rear case), an antenna **370**, and a rear plate **311**. The mobile electronic device **300** may omit at least one (e.g., the first support member **3211** or the second support member **360**) of the above components or may further include another component. Some components of the electronic device **300** may be the same as or similar to those of the mobile electronic device **101** shown in FIG. 1 or FIG. 2, thus, descriptions thereof are omitted below.

(90) The first support member **3211** is disposed inside the mobile electronic device **300** and may be connected to, or integrated with, the lateral bezel structure **320**. The first support member **3211** may be formed of, for example, a metallic material and/or a non-metal (e.g., polymer) material. The first support member **3211** may be combined with the display **301** at one side thereof and also combined with the printed circuit board (PCB) **340** at the other side thereof. On the PCB **340**, a processor, a memory, and/or an interface may be mounted. The processor may include, for example, one or more of a central processing unit (CPU), an application processor (AP), a graphics processing unit (GPU), an image signal processor (ISP), a sensor hub processor, or a communications processor (CP).

(91) The memory may include, for example, one or more of a volatile memory and a non-volatile memory.

(92) The interface may include, for example, a high definition multimedia interface (HDMI), a USB interface, a secure digital (SD) card interface, and/or an audio interface. The interface may electrically or physically connect the mobile electronic device **300** with an external electronic device and may include a USB connector, an SD card/multimedia card (MMC) connector, or an audio connector.

(93) The battery **350** is a device for supplying power to at least one component of the mobile electronic device **300**, and may include, for example, a non-rechargeable primary battery, a rechargeable secondary battery, or a fuel cell. At least a part of the battery **350** may be disposed on substantially the same plane as the PCB **340**. The battery **350** may be integrally disposed within the mobile electronic device **300**, and may be detachably disposed from the mobile electronic device **300**.

(94) The antenna **370** may be disposed between the rear plate **311** and the battery **350**. The antenna **370** may include, for example, a near field communication (NFC) antenna, a wireless charging

antenna, and/or a magnetic secure transmission (MST) antenna. The antenna **370** may perform short-range communication with an external device, or transmit and receive power required for charging wirelessly. An antenna structure may be formed by a part or combination of the lateral bezel structure **320** and/or the first support member **3211**.

(95) FIG. **4A** is a diagram illustrating a structure of, for example, a third antenna module described with reference to FIG. **2** according to an embodiment of the disclosure.

(96) Referring to FIG. **4A**, view (a) is a perspective view illustrating the third antenna module **246** viewed from one side, and FIG. **4A**, view (b) is a perspective view illustrating the third antenna module **246** viewed from the other side. FIG. **4A**, view (c) is a cross-sectional view illustrating the third antenna module **246** taken along line X-X' of FIG. **4A**.

(97) With reference to FIG. **4A**, in one embodiment, the third antenna module **246** may include a printed circuit board **410**, an antenna array **430**, an RFIC **452**, and a PMIC **454**. Alternatively, the third antenna module **246** may further include a shield member **490**. In other embodiments, at least one of the above-described components may be omitted or at least two of the components may be integrally formed.

(98) The printed circuit board **410** may include a plurality of conductive layers and a plurality of non-conductive layers stacked alternately with the conductive layers. The printed circuit board **410** may provide electrical connections between the printed circuit board **410** and/or various electronic components disposed outside using wirings and conductive vias formed in the conductive layer.

(99) The antenna array **430** (e.g., **248** of FIG. **2**) may include a plurality of antenna elements **432**, **434**, **436**, and/or **438** disposed to form a directional beam. As illustrated, the antenna elements **432**, **434**, **436**, and/or **438** may be formed at a first surface of the printed circuit board **410**. According to another embodiment, the antenna array **430** may be formed inside the printed circuit board **410**.

According to the embodiment, the antenna array **430** may include the same or a different shape or kind of a plurality of antenna arrays (e.g., dipole antenna array and/or patch antenna array).

(100) The RFIC **452** (e.g., the third RFIC **226** of FIG. **2**) may be disposed at another area (e.g., a second surface opposite to the first surface) of the printed circuit board **410** spaced apart from the antenna array. The RFIC **452** is configured to process signals of a selected frequency band transmitted/received through the antenna array **430**. According to one embodiment, upon transmission, the RFIC **452** may convert a baseband signal obtained from a communication processor (not shown) to an RF signal of a designated band. Upon reception, the RFIC **452** may convert an RF signal received through the antenna array **430** to a baseband signal and transfer the baseband signal to the communication processor.

(101) According to another embodiment, upon transmission, the RFIC **452** may up-convert an IF signal (e.g., about 9 GHz to about 11 GHz) obtained from an intermediate frequency integrate circuit (IFIC) (e.g., **228** of FIG. **2**) to an RF signal of a selected band. Upon reception, the RFIC **452** may down-convert the RF signal obtained through the antenna array **430**, convert the RF signal to an IF signal, and transfer the IF signal to the IFIC.

(102) The PMIC **454** may be disposed in another partial area (e.g., the second surface) of the printed circuit board **410** spaced apart from the antenna array **430**. The PMIC **454** may receive a voltage from a main PCB (not illustrated) to provide power necessary for various components (e.g., the RFIC **452**) on the antenna module.

(103) The shielding member **490** may be disposed at a portion (e.g., the second surface) of the printed circuit board **410** so as to electromagnetically shield at least one of the RFIC **452** or the PMIC **454**. According to one embodiment, the shield member **490** may include a shield can.

(104) Although not shown, in various embodiments, the third antenna module **246** may be electrically connected to another printed circuit board (e.g., main circuit board) through a module interface. The module interface may include a connecting member, for example, a coaxial cable connector, board to board connector, interposer, or flexible printed circuit board (FPCB). The RFIC **452** and/or the PMIC **454** of the antenna module may be electrically connected to the printed circuit

board through the connection member.

(105) FIG. 4B is a cross-sectional view illustrating the third antenna module **246** taken along line Y-Y' of FIG. 4A, view (a) according to an embodiment of the disclosure.

(106) Referring to FIG. 4B, the printed circuit board **410** of the illustrated embodiment may include an antenna layer **411** and a network layer **413**. The antenna layer **411** may include at least one dielectric layer **437-1**, and an antenna element **436** and/or a power feeding portion **425** formed on or inside an outer surface of a dielectric layer. The power feeding portion **425** may include a power feeding point **427** and/or a power feeding line **429**.

(107) The network layer **413** may include at least one dielectric layer **437-2**, at least one ground layer **433**, at least one conductive via **435**, a transmission line **423**, and/or a power feeding line **429** formed on or inside an outer surface of the dielectric layer.

(108) Further, in the illustrated embodiment, the RFIC **452** (e.g., the third RFIC **226** of FIG. 2) of FIG. 4A, view (c) may be electrically connected to the network layer **413** through, for example, first and second solder bumps **440-1** and **440-2**. In other embodiments, various connection structures (e.g., solder or ball grid array (BGA)) instead of the solder bumps may be used. The RFIC **452** may be electrically connected to the antenna element **436** through the first solder bump **440-1**, the transmission line **423**, and the power feeding portion **425**. The RFIC **452** may also be electrically connected to the ground layer **433** through the second solder bump **440-2** and the conductive via **435**. Although not illustrated, the RFIC **452** may also be electrically connected to the above-described module interface through the power feeding line **429**. FIG. 5 is a perspective view showing an antenna module according to an embodiment of the disclosure.

(109) An antenna module **500** of FIG. 5 may be similar to, at least in part, the third antenna module **246** of FIG. 2, or may include other embodiments of the antenna module.

(110) Referring to FIG. 5, the antenna module **500** may include an antenna structure composed of a printed circuit board (PCB) **590** and a plurality of conductive patches **510**, **520**, **530**, and **540**. According to an embodiment, the antenna module **500** may include a wireless communication circuit **595** mounted on the PCB **590**. According to an embodiment, the antenna structure may include the plurality of conductive patches **510**, **520**, **530**, and **540** disposed on the PCB **590**. According to an embodiment, the antenna module **500** may include an array antenna AR1 composed of the plurality of conductive patches **510**, **520**, **530**, and **540**. According to an embodiment, the plurality of conductive patches **510**, **520**, **530**, and **540** may be formed on the PCB **590**. According to an embodiment, the PCB **590** may have a first surface **591** facing a first direction (denoted by {circle around (1)}) and a second surface **592** facing a second direction (denoted by {circle around (2)}) opposite to the first direction. According to an embodiment, the antenna module **500** may include the wireless communication circuit **595** disposed on the second surface **592** of the PCB **590**. In another embodiment, the wireless communication circuit **595** may be spaced apart from the PCB **590** in an inner space of the electronic device and electrically connected to the PCB **590** through an electrical connection member (e.g., a flexible PCB (FPCB)). According to an embodiment, the plurality of conductive patches **510**, **520**, **530**, and **540** may be electrically connected to the wireless communication circuit **595**. According to an embodiment, the wireless communication circuit **595** may be configured to transmit and/or receive a radio frequency signal in the range of about 3 GHz to 100 GHz via the array antenna AR1.

(111) According to various embodiments, the plurality of conductive patches **510**, **520**, **530**, and **540** may include a first conductive patch **510**, a second conductive patch **520**, a third conductive patch **530**, and a fourth conductive patch **540** which are disposed at regular intervals on the first surface **591** of the PCB **590** or near the first surface **591** in the PCB **590**. The conductive patches **510**, **520**, **530**, and **540** may have the substantially same configuration. Although the antenna module **500** according to an embodiment is illustrated and described as including the array antenna AR1 composed of four conductive patches **510**, **520**, **530**, and **540**, this is only and should not be construed as a limitation. Alternatively, the antenna module **500** may include, as the array antenna

AR1, one, two, three, five, or more conductive patches. In another embodiment, the antenna module may further include a plurality of conductive patterns (e.g., a dipole antenna) disposed on the PCB 590. In this case, the conductive patterns may be arranged to form a beam pattern direction different from (e.g., perpendicular to) a beam pattern direction of the conductive patches 510, 520, 530, and 540. Although not shown, the antenna module 500 may further include a protective member (e.g., urethane resin) surrounding the wireless communication circuit 595 on the second surface 592 of the PCB 590 and/or a conductive coating member (e.g., electro-magnetic interference (EMI) shielding material) coated on the outer surface of the protective member to shield noise.

(112) FIG. 6A is an exploded perspective view showing an antenna module and a conductive member to be applied thereto according to an embodiment of the disclosure.

(113) FIG. 6B is a perspective view showing an antenna module and a conductive member applied thereto according to an embodiment of the disclosure.

(114) Referring to FIGS. 6A and 6B, an electronic device (e.g., the electronic device 300 in FIG. 3A) may include a conductive member 550 fixed, at least in part, to the antenna module 500.

According to an embodiment, the conductive member 550 may be fixed to a conductive portion (e.g., a conductive portion 321 in FIG. 7) of a housing (e.g., the housing 310 in FIGS. 3A and 7) and/or to a conductive portion of a support member (e.g., the first support member 3211 in FIG. 7) in an inner space of the electronic device. According to an embodiment, the conductive member 550 may be in physical contact with a conductive portion (e.g., the conductive portion 321 in FIG. 7) of a lateral member (e.g., the lateral member 320 in FIG. 7) and thereby reinforce the rigidity of the antenna module 500. According to an embodiment, the conductive member 550 may be formed of a metal material such as stainless steel (SUS), copper (Cu), or aluminum (Al) and thereby effectively transmit a high-temperature heat emitted from the antenna module 500 to the outside.

(115) According to various embodiments, the conductive member 550 may include a first support part 551 facing, at least in part, (e.g., facing the lateral surface of) the PCB 590, and a second support part 552 extended from the first support part 551 and bent to face another portion (e.g., the second surface 592) of the PCB 590. According to an embodiment, the conductive member 550 may include at least one extension part 5511 and 5512 extended from at least one end of the first support part 551 and fixed to the conductive portion (e.g., the conductive portion 321 in FIG. 7) of the lateral member (e.g., the lateral member 320 in FIG. 7) and/or to the conductive portion of the support member (e.g., the first support member 3211 in FIG. 7). In an embodiment, the at least one extension part 5511 and 5512 may include a pair extended in opposite directions of the conductive member 550. In another embodiment, the at least one extension part 5511 and 5512 may be extended from the second support part 552. Therefore, the antenna module 500 may be supported by the first and second support parts 551 and 552 of the conductive member 550 and fixed to the conductive portion (e.g., the conductive portion 321 in FIG. 7) of the lateral member (e.g., the lateral member 320 in FIG. 7) and/or to the conductive portion of the support member (e.g., the first support member 3211 in FIG. 7) through the at least one extension part 5511 and 5512 by a fastening member such as a screw.

(116) FIG. 7 is a cross-sectional view partially showing an electronic device, viewed from line A-A' in FIG. 3B, according to an embodiment of the disclosure.

(117) Referring to FIG. 7, the electronic device 300 may include the housing 310 that includes the front plate 302 (e.g., a front cover) facing a first direction (e.g., the -Z direction), the rear plate 311 (e.g., a rear cover) facing a direction (e.g., the Z direction) opposite to the front plate 302, and the lateral member 320 surrounding an inner space 3001 between the front plate 302 and the rear plate 311. According to an embodiment, the lateral member 320 may include a conductive portion 321 (e.g., a metal member) disposed at least in part and a non-conductive portion 322 (e.g., a polymer member) insert-injected into the conductive portion 321. In another embodiment, the non-conductive portion 322 may be replaced with a space or any other dielectric material. In still

another embodiment, the non-conductive portion **322** may be structurally combined with the conductive portion **321**. According to an embodiment, the lateral member **320** may include a support member **3211** (e.g., the first support member **3211** in FIG. 3C) extended partially into the inner space **3001**. According to an embodiment, the first support member **3211** may be extended from the lateral member **320** into the inner space **3001** or formed by a structural combination with the lateral member **320**. According to an embodiment, the first support member **3211** may be extended from the conductive portion **321**. According to an embodiment, the support member **3211** may support at least a portion of the antenna module **500** disposed in the inner space **3001**. According to an embodiment, the first support member **3211** may be disposed to support at least a portion of a display **301**. According to an embodiment, the display **301** may be disposed to be visible from the outside through at least a portion of the front plate **302**. According to an embodiment, the display **301** may include a flexible display.

(118) According to various embodiments, the antenna module **500** may be disposed in a direction perpendicular to the front plate **302** in the inner space **3001** of the electronic device **300**. According to an embodiment, the antenna module **500** may be mounted such that the array antenna **AR1** including conductive patches (e.g., the conductive patches **510**, **520**, **530**, and **540** in FIG. 5A) faces the lateral member **320**. For example, the antenna module **500** may be disposed such that the first surface **591** of the PCB **590** faces the lateral member **320** and thus a beam pattern is formed in a direction (denoted by {circle around (1)}) faced by the lateral member **320**. According to an embodiment, at least a portion of the lateral member **320** faced by the antenna module **500** may be formed as the non-conductive portion **322** such that a beam pattern is formed in a direction (denoted by {circle around (1)}) faced by the lateral member **320**. According to an embodiment, the electronic device **300** may include a device substrate **340** (e.g., the PCB **340** in FIG. 3C) disposed in the inner space **3001**. According to an embodiment, although not shown, the antenna module **500** may be electrically connected to the device substrate **340** through an electrical connection member (e.g., an FPCB connector).

(119) FIG. 8A is a view partially showing an electronic device, viewed from line B-B' in FIG. 3B, according to an embodiment of the disclosure.

(120) FIG. 8A shows only the conductive portion **321** when the rear plate **311** is viewed from above, while substantially omitting the non-conductive portion **322**. The non-conductive portion **322** may be filled with an insulating member such as a polymer member.

(121) Referring to FIG. 8A, the lateral member **320** may include the non-conductive portion **322** (e.g., a polymer member) disposed to correspond to a region where a beam pattern of the antenna module **500** is formed. According to an embodiment, the non-conductive portion **322** may be insert-injected into the conductive portion **321**. According to an embodiment, a boundary region between the non-conductive portion **322** and the conductive portion **321** may be disposed near the antenna module **500**. According to an embodiment, the boundary region may have an engaging structure for disallowing the conductive portion **321** and the non-conductive portion **322**, after combined with each other, to be separated from each other by external impact. According to an embodiment, the boundary region may be placed at a position which is not overlapped with the antenna module **500** when the lateral member **320** is viewed from the outside. For example, the conductive portion **321** may include a concave portion **3221** formed concavely in the boundary region. According to an embodiment, the non-conductive portion **322** may be formed as a part of the lateral member **320** of the electronic device **300** by being filled in the concave portion **3221** through insert injection.

(122) According to various embodiments, when the concave portion **3221** is formed deeper than a predetermined depth, an excitation current may be generated by a current trap phenomenon through the concave portion **3221**. This excitation current may degrade the radiation performance of the antenna module **500**. Therefore, the depth and/or shape of the concave portion **3221** may become important parameters in determining the antenna radiation performance.

(123) According to various embodiments, when the rear plate **311** is viewed from above as in FIG. **3B**, the concave portion **3221** may be formed such that an inclined angle (θ) thereof does not exceed about 60 degrees. As illustrated, the inclined angle (θ) is an angle formed by a starting point of the concave portion **3221** (i.e., a contact point with the lateral member **320**) with respect to a virtual line (L) formed from both ends of the PCB **590** toward the lateral member **320** (i.e., in a direction perpendicular to the lateral member **320** as denoted by {circle around (1)}). In addition, having the inclined angle (θ) does not exceed about 60 degrees, the concave portion **3221** may be formed at a certain depth and in a certain shape. The shape of the concave portion **3221** may be varied such as a curved shape or a flat shape. In a certain embodiment, the concave portion **3221** may be formed such that the inclined angle (θ) does not exceed about 60 degrees with respect to a virtual line (L) formed from both ends of the array antenna **AR1** toward the lateral member **320**. According to an embodiment, the inclined angle (θ) of the concave portion **3221** may range from about 30 degrees to about 60 degrees in consideration of beam coverage (e.g., ± 30 degrees with respect to the virtual line (L)) of the array antenna **AR1**. According to an embodiment, the concave portion **3221** may be gradually narrowed or widened along the inclination angle (θ) with respect to the virtual line (L). According to an embodiment, the inner surface of the concave portion **3221** may be a curved plane having a specific radius of curvature.

(124) According to an embodiment, the concave portion **3221** may prevent an unwanted separation between the non-conductive portion **322** and the conductive portion **321** in a horizontal direction (denoted by {circle around (1)}) by external impact. According to an embodiment, the concave portion **3221** may have at least one slit **3221a** further recessed from the inner surface of the concave portion **3221**. According to an embodiment, the slit **3221a** may be formed in a direction substantially parallel to the rear plate **311**. According to an embodiment, the slit **3221a** may increase a contact area between the conductive portion **321** and the non-conductive portion **322** and thereby improve an engaging force. According to an embodiment, the slit **3221a** may prevent an unwanted separation between the non-conductive portion **322** and the conductive portion **321** in a vertical direction (denoted by {circle around (3)}) by external impact. According to an embodiment, the radiation characteristics of the antenna module **500** may be determined depending on the shape, depth, width, and/or number of the slits **3221a**.

(125) According to various embodiments, a distance (d) between the concave portion **3221** and the PCB **590**, as illustrated, may be determined so as not to exceed a quarter of wavelength (i.e., $\frac{1}{4} \times \lambda$) in the greatest operating frequency wavelength carrier of the antenna module.

(126) FIG. **8B** is a view partially showing a lateral member having a non-conductive region around an antenna module according to an embodiment of the disclosure.

(127) Referring to FIG. **8B**, the lateral member **320** may include, in the conductive portion **321**, at least one non-conductive region **322a** disposed around the antenna module **500**. According to an embodiment, the at least one non-conductive region **322a** may be disposed near both right and left ends of the PCB **590** of the antenna module **500** when the lateral member **320** is viewed from the outside. According to an embodiment, the at least one non-conductive region **322a** may be formed to cross, at least in part, the lateral member **320** between the PCB **590** and the concave portion **3221**. According to an embodiment, the at least one non-conductive region **322a** may be formed through injection of the same material as or a different material from that of the non-conductive portion **322**. The at least one non-conductive region **322a** may prevent a double radiation phenomenon caused by the concave portion **3221** when a beam is emitted from the array antenna **AR1**.

(128) FIGS. **9A** and **9B** are graphs showing radiation patterns and gains by horizontal polarization (H-pol) of an antenna module according to various embodiments of the disclosure.

(129) Referring to FIGS. **9A** and **9B**, compared to horizontal polarization **901** and gain **903** of a typical antenna module in which a concave portion has an inclined angle (θ) that exceeds about 60 degrees, horizontal polarization **902** and gain **904** of the antenna module **500** according to an

embodiment of the disclosure exhibit relatively excellent sensitivity characteristics and gain improved by about 2.5 dB. The reason is that, as described above with reference to FIGS. 7 and 8A, a concave portion (e.g., the concave portion 3221 in FIG. 8A) is formed in a conductive portion (e.g., the conductive portion 321 in FIG. 8A) such that an inclined angle (θ) thereof does not exceed about degrees.

(130) FIG. 9C is a graph showing a radiation pattern by vertical polarization (V-pol) of an antenna module according to an embodiment of the disclosure.

(131) Referring to FIG. 9C, compared to vertical polarization 905 of a typical antenna module in which a concave portion has an inclined angle (θ) that exceeds about degrees, vertical polarization 906 of the antenna module 500 according to an embodiment of the disclosure exhibit relatively excellent sensitivity characteristics. The reason is that, as described above with reference to FIGS. 7 and 8A, a concave portion (e.g., the concave portion 3221 in FIG. 8A) is formed in a conductive portion (e.g., the conductive portion 321 in FIG. 8A) such that an inclined angle (θ) thereof does not exceed about 60 degrees.

(132) FIG. 10 is a cross-sectional view partially showing an electronic device, viewed from line C-C' in FIG. 3A, according to an embodiment of the disclosure.

(133) FIG. 11A is a perspective view partially showing a housing according to an embodiment of the disclosure.

(134) In the following description of the electronic device 300, the same components as those described above are denoted by the same reference numerals, and detailed descriptions thereof may be omitted.

(135) According to various embodiments, in the antenna module 500 that performs radiation in a direction (denoted by {circle around (1)}) facing from the inner space 3001 of the electronic device 300 to the lateral member 320, a cancelation phenomenon (or null phenomenon) may occur due to a phase difference between a beam pattern directly radiated from the antenna module 500 and a beam pattern reflected by the first support member 3211 disposed nearby. This may degrade the radiation performance of the antenna module 500. Various embodiments of the disclosure may have a configuration for preventing the performance degradation of the antenna through a structural change of the lateral member 320.

(136) Referring to FIGS. 10 and 11A, the electronic device 300 may include the housing 310 that includes the front plate 302 (e.g., a front cover), the rear plate 311 (e.g., a rear cover) facing a direction opposite to the front plate 302, and the lateral member 320 surrounding the inner space 3001 between the front plate 302 and the rear plate 311. According to an embodiment, the lateral member 320 may have a first surface 3201 facing the front plate 302, and a second surface 3202 facing a direction opposite to the first surface 3201. According to an embodiment, the lateral member 320 may include the conductive portion 321 (e.g., a metal member) disposed at least in part, and a first non-conductive portion 3224 (e.g., the non-conductive portion 322 in FIG. 7, e.g., a polymer member) insert-injected into the conductive portion 321. According to an embodiment, the lateral member 320 may include the support member 3211 (e.g., the first support member 3211 in FIG. 3C) extended at least partially into the inner space 3001.

(137) According to various embodiments, the front plate 302 may be disposed on the first surface 3201 of the lateral member 320. According to an embodiment, the front plate 302 may be supported by at least a part of the lateral member 320 including the first support member 3211. According to an embodiment, the electronic device 300 may include a display 301 disposed between the front plate 302 and the lateral member 320. According to an embodiment, the display 301 may include a polarization layer (not shown), a display panel (not shown), at least one additional layer (e.g., a cushion layer and/or an embossing layer, not shown), and/or a conductive sheet 3011, which are stacked sequentially on the rear surface of the front plate 302. According to an embodiment, the display 301 may include the conductive sheet 3011 (e.g., a Cu sheet) disposed for noise shielding on the rear surface of the display panel.

(138) According to various embodiments, the antenna module **500** may be disposed in a direction perpendicular to the front plate **302** in the inner space **3001** of the electronic device **300** through a conductive member **550**. According to an embodiment, the antenna module **500** may be mounted such that an array antenna **AR1** including conductive patches (e.g., the conductive patches **510**, **520**, **530**, and **540** in FIG. 5A) (e.g., a plurality of antenna elements) face the lateral member **320**. For example, the antenna module **500** may be disposed such that a first surface **591** of a PCB **590** faces the lateral member **320**, and thus a beam pattern may be formed in a direction (denoted by {circle around (1)}) faced by the lateral member **320** of the electronic device **300**. According to an embodiment, at least a part of the lateral member **320** facing the antenna module **500** may be the first non-conductive portion **3224** that allows a beam pattern to be formed in the direction (denoted by {circle around (1)}) faced by the lateral member **320**. According to an embodiment, the electronic device **300** may include a device substrate **340** (e.g., the PCB **340** in FIG. 3C) disposed in the inner space **3001**. According to an embodiment, although not shown, the antenna module **500** may be electrically connected to the device substrate **340** through an electrical connector (e.g., an FPCB connector).

(139) According to various embodiments, at least a part of the conductive portion **321** of the lateral member **320** may be formed in a shape for supporting the display **301** and the front plate **302** above one side of the antenna module **500**. Therefore, the conductive portion **321** of the lateral member **320** may affect, at least in part, a beam pattern radiated in a direction of the front plate **302**.

(140) According to various embodiments, the lateral member **320** may further include at least one second non-conductive portion **3222** disposed at a position corresponding to the array antenna **AR1** of the antenna module **500** in the direction of the front plate **302**. According to an embodiment, the second non-conductive portion **3222** may be inserted-injected together with the first non-conductive portion **3224** (e.g., the non-conductive portion **322** in FIG. 7) into the conductive portion **321**. In another embodiment, the first non-conductive portion **3224** and the second non-conductive portion **3222** may be formed of insulating materials having different properties (e.g., different dielectric constants). In still another embodiment, the second non-conductive portion **3222** may be an empty space in which no insulating material is disposed. The second non-conductive portion **3222** may be formed in the first surface **3201** (e.g., a flat portion) of the lateral member **320** and/or a curved surface extended laterally from the first surface **3201**. According to an embodiment, the at least one second non-conductive portion **3222** may be disposed at a position overlapped at least in part with the array antenna **AR1** when the front plate **302** is viewed from above and/or when the lateral member **320** is viewed from outside. According to an embodiment, a plurality of second non-conductive portions **3222** may be disposed at positions corresponding to respective conductive patches (e.g., the first conductive patch **510**, the second conductive patch **520**, the third conductive patch **530**, and/or the fourth conductive patch **540** in FIG. 5). Therefore, a beam pattern radiated from the antenna module **500** in the direction of the lateral member **320** is increased upward in radiation length up to the conductive sheet **3011** of the display **301** through the second non-conductive portion **3222**. This may help to reduce the cancelation phenomenon as compared to an antenna module disposed near the lateral member **320** having no second non-conductive portion **3222**.

(141) FIG. 11B is a perspective view partially showing a housing according to an embodiment of the disclosure.

(142) Referring to FIG. 11B, the lateral member **320** may include a second non-conductive portion **3223** disposed in the first surface **3201** and/or a curved surface extended laterally from the first surface **3201**. According to an embodiment, the second non-conductive portion **3223** may be formed in a size overlapped at least in part with a plurality of conductive patches (e.g., the first conductive patch **510**, the second conductive patch **520**, the third conductive patch **530**, and/or the fourth conductive patch **540** in FIG. 5) of the array antenna **AR1** when the front plate **302** is viewed from above and/or when the lateral member **320** is viewed from outside.

(143) FIGS. **12A** and **12B** are graphs showing radiation patterns and gains by horizontal polarization (H-pol) of the antenna module of FIG. **10** according to various embodiments of the disclosure.

(144) Referring to FIGS. **12A** and **12B**, compared to horizontal polarization **1201** and gain **1203** of a typical antenna module in which a lateral member has a conductive portion, horizontal polarization **1202** and gain **1204** of the antenna module (e.g., the antenna module **500** in FIG. **10**) according to an embodiment of the disclosure exhibit relatively excellent sensitivity characteristics and high gain. The reason is that, as described above, a lateral member (e.g., the lateral member **320** in FIG. **10**) of the antenna module according to an embodiment may include a second non-conductive portion (e.g., the second non-conductive portion **3222** in FIG. **10**) disposed at a position overlapped at least in part with an array antenna (e.g., the array antenna **AR1** in FIG. **10**) when a front plate (e.g., the front plate **302** in FIG. **10**) is viewed from above and/or when the lateral member is viewed from outside.

(145) FIG. **13** is a cross-sectional view partially showing an electronic device including a conductive connection member according to an embodiment of the disclosure.

(146) Referring to FIG. **13**, when an antenna module (e.g., the antenna module **500** in FIG. **10**) operates through the lateral member **320** including a second non-conductive portion (e.g., the second non-conductive portion **3222** in FIG. **10**), a beam form of vertical polarization (V-pol) may be distorted by a conductive sheet **3011** (e.g., a Cu sheet) disposed on a rear surface of a display **301** (e.g., a display panel). According to an embodiment of the disclosure, in order to suppress such a beam form distortion of vertical polarization, the electronic device **300** may include at least one conductive connection member **3212** disposed between a conductive portion **321** of the lateral member **320** and the conductive sheet **3011**. According to an embodiment, the conductive connection member **3212** may be disposed to be in physical contact with both the conductive sheet **3011** and the conductive portion **321** of the lateral member **320**. According to an embodiment, the conductive connection member **3212** may be formed of a metal member. Thus, the conductive sheet **3011** electrically connected to the conductive member **321** through the conductive connection member **3212** may be seen as at least a part of the conductive member **321** disposed near the antenna module **500**.

(147) According to various embodiments, the antenna module **500** may be configured to allow vertical polarization (V-pol) to be adjusted independently without substantial change of horizontal polarization (H-pol) through a movement of the conductive connection member **3212** between the conductive sheet **3011** and the lateral member **320**.

(148) FIG. **14A** is a radiation pattern view showing horizontal polarization (H-pol) of an antenna module before and after a movement of a conductive connection member according to an embodiment of the disclosure.

(149) Referring to FIG. **14A**, even if the conductive connection member **3212** is moved between the conductive sheet **3011** and the lateral member **320**, horizontal polarization **1402** after movement may be exhibited at the same position as horizontal polarization **1401** before movement. This means that even when the conductive connection member **3212** is moved, the horizontal polarization (H-pol) may be substantially fixed.

(150) FIG. **14B** is a radiation pattern view showing vertical polarization (V-pol) of an antenna module before and after a movement of a conductive connection member according to an embodiment of the disclosure.

(151) As shown in FIG. **13**, when the conductive connection member **3212** is moved from a first position (P1) to a second position (P2) between the conductive sheet **3011** and the lateral member **320**, vertical polarization (V-pol) may be adjusted. Referring to FIG. **14B**, vertical polarization **1403** in case where the conductive connection member **3212** of FIG. **13** is not applied, vertical polarization **1404** before movement of the conductive connection member **3212** of FIG. **13**, and vertical polarization **1405** after the movement are all different from each other. This may mean that

independent tuning of vertical polarization (V-pol) is possible depending on the presence and/or movement of the conductive connection member **3212**.

(152) FIG. **15** is a perspective view partially showing an electronic device including a conductive sheet having a notch according to an embodiment of the disclosure.

(153) Referring to FIG. **15**, when the antenna module (e.g., the antenna module **500** in FIG. **10**) operates through the lateral member **320** in the electronic device including the second non-conductive portion **3222** and the conductive connection member **3212** as described above in FIG. **13**, the sensitivity may be degraded by the conductive sheet **3011** (e.g., a Cu sheet) disposed on the rear surface of the display **301**. In order to prevent such a degradation of sensitivity, the electronic device **300** may include, for example, a notch **3012** formed in at least a part of the conductive sheet **3011**. According to an embodiment, the notch **3012** may have a region overlapped with the second non-conductive area **3222** when the front plate **302** is viewed from above. According to an embodiment, in the inner space **3001** of the electronic device **300**, the antenna module (e.g., the antenna module **500** in FIG. **10**) may form a beam pattern in the direction of the display **301** through the second non-conductive portion **3222** formed in the lateral member **320** and the notch **3012** formed in the conductive sheet **3011**.

(154) FIG. **16** is a graph showing radiation patterns by vertical polarization (V-pol) and horizontal polarization (H-pol) of an antenna module (e.g., the antenna module **500** in FIG. **10**) disposed in the electronic device of FIG. **15** according to an embodiment of the disclosure.

(155) Referring to FIG. **16**, in the antenna module (e.g., the antenna module **500** in FIG. **10**), vertical polarization **1602** in case where a notch region (e.g., the notch **3012** in FIG. **15**) is applied to a conductive sheet (e.g., the conductive sheet **3011** in FIG. **15**) exhibits a relatively excellent sensitivity characteristic compared to vertical polarization **1601** in case where the notch region is not applied. In addition, horizontal polarization **1604** in case where the notch region is applied to the conductive sheet exhibits a relatively excellent sensitivity characteristic compared to horizontal polarization **1603** in case where the notch region is not applied.

(156) FIG. **17** is a cross-sectional view partially showing an electronic device according to an embodiment of the disclosure.

(157) According to a certain embodiment, it is possible to prevent the performance degradation of the antenna module **500** by changing the structural shape of the inner surface of the conductive portion **321** of the lateral member **320**.

(158) Referring to FIG. **17**, the electronic device **300** may include the conductive portion **321** disposed as a part of the lateral member **320** near one upper side of the antenna module **500** placed in the inner space **3001**, and supporting at least in part the front plate **302** and the display **301**. According to an embodiment, in the lateral member **320**, a typical shape of the conductive portion **321** such as a first-stage structure (e.g., a first-stage eaves structure) or a stepped structure (e.g., a two-stage eaves structure) is changed to increase (delay with 180 degrees) or decrease a phase difference between radio waves directly radiated to the outside from the antenna module **500** and radio waves reflected by the inner surface of the conductive portion **321**. As a result, it is possible to prevent the cancelation phenomenon (or null phenomenon) occurring when radio waves having different phases gather around one place.

(159) According to various embodiments, the conductive portion **321** of the lateral member **320** may include a structural shape for not only distorting an effective direction of radio waves radiated from the antenna module **500** and reflected by the conductive portion **321**, but also increasing a path length. According to an embodiment, the conductive portion **321** may include a first flat plane **3203**, a curved plane **3204** extended laterally from the first flat plane **3203**, and a second flat plane **3205** extended from the curved plane **3204**. According to an embodiment, the first flat plane **3203** and/or the second flat plane **3205** may be formed to be substantially perpendicular to the first surface **591** of the PCB **590**. In another embodiment, the first flat plane **3203** and/or the second flat plane **3205** may be formed to have various inclination angles that allow radio waves (E) radiated

from the antenna module **500** and reflected by the conductive portion **321** to be scattered without gathering around one place. In still another embodiment, the curved plane **3204** may be formed to have various radii of curvature that allow the radio waves (E) radiated from the antenna module **500** and reflected by the conductive portion **321** to be scattered without gathering around one place. In yet another embodiment, the conductive portion **321** may have, at least in part, a thickness (t) adjusted to increase the path length of the radio waves (E) radiated from the antenna module **500**. (160) FIG. **18** is a cross-sectional view partially showing an electronic device according to an embodiment of the disclosure.

(161) FIGS. **19A** and **19B** are perspective views partially showing a support member according to various embodiments of the disclosure.

(162) An electronic device **600** of FIG. **18** may be similar, at least in part, to the electronic device **101** of FIG. **1**, the electronic device **300** of FIG. **3A**, or the electronic device **300** of FIG. **10**, or may include other embodiments of the electronic device.

(163) Referring to FIGS. **18** and **19A**, the electronic device **600** may include a housing **610** (e.g., the housing **310** in FIG. **10**) that includes a front cover **602** (e.g., the front plate **302** in FIG. **10**), a rear cover **611** (e.g., the rear plate **311** in FIG. **10**) facing a direction opposite to the front cover **602**, and a support member **620** (e.g., the lateral member **320** in FIG. **10**) surrounding an inner space **6001** between the front cover **602** and the rear cover **611**. According to an embodiment, the electronic device **600** may include a device substrate **640** (e.g., the PCB **340** in FIG. **3C**) disposed in the inner space **6001**. According to an embodiment, the support member **620** may include a conductive first portion **621** forming a lateral appearance (e.g., the lateral surface **310c** in FIG. **3A**) of the electronic device **600**, a second portion **622** adjacent to an array antenna **AR1**, the front cover **602**, and the conductive first portion **621** and having at least one opening **6221** filled with a non-conductive material, and a third portion **623** formed of a non-conductive material and adjacent to the array antenna **AR1**, the rear cover **611**, and the conductive first portion **621**. According to an embodiment, the support member **620** may be disposed between the front and rear covers **602** and **611**, support a display **601** of the electronic device **600**, and extended toward the lateral surface of the electronic device **600** to form, at least in part, the lateral appearance (e.g., the lateral surface **310c** in FIG. **3A**) of the electronic device **600**.

(164) According to various embodiments, the front cover **602** may be disposed through at least parts of the conductive first portion **621** and the second portion **622** of the support member **620**. According to an embodiment, the front cover **602** may be supported through an extended portion **6211** (e.g., the first support member **3211** in FIG. **10**) extended from the support member **620**.

According to an embodiment, the electronic device **600** may include the display **601** disposed between the front cover **602** and the support member **620** to be seen from the outside at least in part through the front cover **602**. According to an embodiment, the display **601** may include a polarization layer (not shown), a display panel (not shown), at least one additional layer (e.g., a cushion layer and/or an embossing layer, not shown), and/or a conductive sheet **6011** (e.g., the conductive sheet **3011** in FIG. **10**), which are stacked sequentially on the rear surface of the front cover **602**. According to an embodiment, the display **601** may include the conductive sheet **6011** (e.g., a Cu sheet) disposed for noise shielding on the rear surface of the display panel.

(165) According to various embodiments, the antenna module **500** may be disposed in a direction perpendicular to the front cover **602** in the inner space **6001** of the electronic device **600** through the conductive member **550**. According to an embodiment, the antenna module **500** may be mounted such that the array antenna **AR1** including conductive patches (e.g., the conductive patches **510**, **520**, **530**, and **540** in FIG. **5A**) (e.g., a plurality of antenna elements) face the support member **620**. For example, the antenna module **500** may be disposed such that the first surface **591** of the PCB **590** faces the support member **620**, and thus a beam pattern may be formed in a direction (denoted by {circle around (1)}) faced by the support member **620** of the electronic device **600**.

(166) According to various embodiments, the conductive first portion **621** and the second portion **622** of the support member **620** may be formed in a shape for supporting the display **601** and the front cover **602** near one upper side of the antenna module **500**. According to an embodiment, the third portion **623** of the support member **620** may be formed in a shape for supporting the rear cover **611** near one lower side of the antenna module **500**. According to an embodiment, the conductive first portion **621** may be exposed at least in part to the outside of the electronic device **600**, and the second and third portions **622** and **623** may be hidden by the front and rear covers **602** and **611** so as not to be exposed to the outside. According to an embodiment, a beam formed by the array antenna AR1 may be radiated to the outside through the at least one opening **6221** and the third portion **623**.

(167) According to various embodiments, the at least one opening **6221** formed in the second portion **622** may be filled with a non-conductive material. For example, the non-conductive material of the second portion **622** and the non-conductive material of the third portion **623** may be inserted-injected together with the conductive first portion **621**. In a certain embodiment, the non-conductive material of the second portion **622** and the non-conductive material of the third portion **623** may be formed of insulating materials having the same or different properties (e.g., different dielectric constants). In a certain embodiment, the non-conductive material of the second portion **622** and the non-conductive material of the third portion **623** may be connected to or spaced apart from each other in the inner space of the electronic device. In a certain embodiment, the at least one opening **6221** may be an empty space in which no insulating material is disposed. According to an embodiment, the second portion **622** may include a flat portion **6201** and a curved portion **6202** extended from the flat portion **6201** to the first portion **621**. According to an embodiment, the at least one opening **6221** and/or the non-conductive material filled in the at least one opening **6221** may be formed in a shape including the flat portion **6201** and/or the curved portion **6202**.

(168) According to an embodiment, the at least one opening **6221** may be disposed at a position overlapped at least in part with the array antenna AR1 when the front cover **602** is viewed from above and/or when the support member **620** is viewed from outside. According to an embodiment, a plurality of openings **6221** may be disposed at positions corresponding to respective conductive patches (e.g., the first conductive patch **510**, the second conductive patch **520**, the third conductive patch **530**, and/or the fourth conductive patch **540** in FIG. 5). Therefore, a beam pattern radiated from the antenna module **500** in the direction (denoted by {circle around (1)}) of the support member **620** is increased upward in radiation length up to the conductive sheet **6011** of the display **601** through the at least one opening **6221**. This may help to reduce the cancelation phenomenon as compared to an antenna module disposed through the support member **620** having no opening **6221**.

(169) Referring to FIG. 19B, the support member **620** may include a single opening **6221** disposed to be overlapped with the array antenna AR1. According to an embodiment, the opening **6221** may be formed in a size overlapped with all of a plurality of conductive patches (e.g., the first conductive patch **510**, the second conductive patch **520**, the third conductive patch **530**, and/or the fourth conductive patch **540** in FIG. 5) of the array antenna AR1 when the front cover **602** is viewed from above and/or when the support member **620** is viewed from outside. Although not shown, the electronic device **600** may include, as in FIG. 13, an electrical connection member (e.g., the electrical connection member **3212** in FIG. 20A) disposed between the conductive first portion **621** and the conductive sheet **6011**. In addition, the radiation characteristics of the array antenna AR1 may be adjusted depending on a change in position of the conductive connection member.

(170) FIGS. 20A and 20B are perspective views partially showing an electronic device including a conductive sheet having a slot according to various embodiments of the disclosure.

(171) Referring to FIGS. 20A and 20B, when the beam pattern of the array antenna AR1 is formed through the at least one opening **6221** shown in FIG. 18, the sensitivity may be degraded by the conductive sheet **6011** (e.g., a Cu sheet) disposed on the rear surface of the display **601**. In order to

prevent such a degradation of sensitivity, the electronic device **600** may include, for example, at least one slot **6011a** or **6011b** formed in at least a part of the conductive sheet **6011**. According to an embodiment, the at least one slot **6011a** or **6011b** may be formed at a position overlapped with the at least one opening **6221** when the front cover **602** is viewed from above. For example, the at least one slot **6011a** or **6011b** may be one slot **6011a** or two slots **6011b** having a length overlapped with a plurality of antenna elements (e.g., conductive patches) of the array antenna **AR1**. In a certain embodiment, the at least one slot may be a plurality of slots respectively corresponding to the plurality of antenna elements.

(172) As described above, the electronic device according to embodiments of the disclosure has the structurally modified housing for disallowing the non-conductive portion thereof to be separated from the conductive portion thereof from external impact. This may also prevent the radiation performance of the antenna from being degraded.

(173) According to various embodiments of the disclosure, an electronic device (e.g., the electronic device **600** in FIG. **18**) may include a front cover (e.g., the front cover **602** in FIG. **18**), a rear cover (e.g., the rear cover **611** in FIG. **18**), an array antenna (e.g., the array antenna **AR1** in FIG. **18**), and a support member (e.g., the support member **620** in FIG. **18**). The front cover and the rear cover may form a part of an outer appearance of the electronic device. The array antenna may include a plurality of antenna elements disposed between the front cover and the rear cover. The support member may be disposed between the front cover and the rear cover, support a display (e.g., the display **601** in FIG. **18**) of the electronic device, and be extended to a lateral surface of the electronic device to form at least in part a lateral appearance of the electronic device. The support member may include a conductive first portion (e.g., the conductive first portion **621** in FIG. **18**) forming the lateral appearance of the electronic device, a second portion (e.g., the second portion **622** in FIG. **18**) adjacent to the array antenna, the front cover, and the conductive first portion, and having at least one opening (e.g., the opening **6221** in FIG. **19A**) filled with a non-conductive material, and a third portion (e.g., the third portion **623** in FIG. **18**) formed of a non-conductive material and adjacent to the array antenna, the rear cover, and the conductive first portion. The first portion may be exposed to an outside of the electronic device, and the second and third portions may be hidden by the front and rear covers so as not to be exposed to the outside. A beam formed by the array antenna may be radiated to the outside through the at least one opening and the third portion.

(174) According to various embodiments, the display may include a display panel disposed between the front cover and the rear cover and overlapped with the at least one opening, and a conductive sheet (e.g., the conductive sheet **6011** in FIG. **18**) disposed on a rear surface of the display panel so as not to be overlapped with the at least one opening.

(175) According to various embodiments, the conductive sheet may include at least one notch (e.g., the notch **3012** in FIG. **15**) or at least one slot (e.g., the slot **6011a** in FIG. **20A** or the slots **6011b** in FIG. **20B**) formed in a region overlapped with the at least one opening.

(176) According to various embodiments, the electronic device may further include a conductive connection member (e.g., the conductive connection member **3212** in FIG. **20A**) disposed between the conductive sheet and the conductive first portion.

(177) According to various embodiments, the conductive connection member may include a metal member electrically connecting the conductive first portion and the conductive sheet.

(178) According to various embodiments, an electrical connecting position of the conductive connection member between the conductive first portion and the conductive sheet may determine radiation characteristics of the array antenna.

(179) According to various embodiments, the conductive first portion and/or the second portion may be disposed to face the front cover, and the conductive first portion and/or the second portion may have a flat portion (e.g., the flat portion **6201** in FIG. **19A**) and a curved portion (e.g., the curved portion **6202** in FIG. **19A**) extended from the flat portion. The display panel and the

conductive sheet may be disposed adjacent to at least a part of the curved portion from the flat portion.

(180) According to various embodiments, the at least one opening may be disposed at least in part in the flat portion and the curved portion.

(181) According to various embodiments, the second portion and the third portion may be disposed at least in part to be connected to each other.

(182) According to various embodiments, the non-conductive material of the second portion and the non-conductive material of the third portion may have same or different dielectric constants.

(183) According to various embodiments, the at least one opening may be disposed at a position corresponding to the plurality of antenna elements.

(184) According to various embodiments, the at least one opening may be formed in a number corresponding to a number of the antenna elements.

(185) According to various embodiments, the plurality of antenna elements may include a plurality of conductive patches disposed at regular intervals on a printed circuit board, and the at least one opening may be formed in a size corresponding to all of the plurality of conductive patches.

(186) According to various embodiments of the disclosure, a portable communication device (e.g., the electronic device **600** in FIG. **18**) may include a housing (e.g., the housing **610** in FIG. **18**), a display (e.g., the display **601** in FIG. **18**), and an antenna module (e.g., the antenna module **500** in FIG. **18**). The housing may include a first member (e.g., the front cover **602** in FIG. **18**) forming a front portion of the portable communication device, a second member (e.g., the rear cover **611** in FIG. **18**) forming a rear portion of the portable communication device, and a third member (e.g., the support member **620** in FIG. **18**) forming a lateral portion of the portable communication device. The third member may include a conductive member (e.g., the conductive first portion **621** in FIG. **18**) having an opening (e.g., the opening **6221** in FIG. **19A**) formed therein, and a non-conductive member (e.g., the second portion **622** in FIG. **18**) filled in the opening. One surface of the conductive member may be exposed to an outside of the portable communication device, and the non-conductive member may be disposed in the housing so as not to be exposed to the outside. The display may be disposed under the first member and visually seen to the outside through the first member. The antenna module may be disposed between the display and the second member and include an antenna (e.g., the array antenna **AR1** in FIG. **18**) and a printed circuit board (e.g., the PCB **590** in FIG. **18**). The antenna may be formed on the printed circuit board such that a signal radiated from the antenna is transmitted to the outside through the non-conductive member.

(187) According to various embodiments, the display may include a display panel and a conductive sheet (e.g., the conductive sheet **6011** in FIG. **18**) disposed on a rear surface of the display panel so as not to be overlapped with the opening.

(188) According to various embodiments, the conductive sheet may have at least one notch (e.g., the notch **3012** in FIG. **15**) or at least one slot (e.g., the slot **6011a** in FIG. **20A** or the slots **6011b** in FIG. **20B**) formed in a region overlapped with the opening.

(189) According to various embodiments, the opening may include a first sub-opening (e.g., the first opening **6221** in FIG. **19A**) and a second sub-opening (e.g., the second opening **6221** disposed near the first opening in FIG. **19A**) spaced apart from each other. An upper surface of the non-conductive member may include a first portion (e.g., the second portion **622** in FIG. **19A**) exposed through the conductive member through the first sub-opening and a second portion (e.g., the second portion **622** in FIG. **19A**) exposed through the conductive member through the second sub-opening.

(190) According to various embodiments, the antenna may include a first antenna (e.g., the first conductive patch **510** in FIG. **5**) and a second antenna (e.g., the second conductive patch **520** in FIG. **5**) spaced from each other. The first portion may be overlapped with the first antenna when viewed in a direction substantially perpendicular to the first portion of the upper surface, and the second portion may be overlapped with the second antenna when viewed in a direction

substantially perpendicular to the second portion of the upper surface.

(191) According to various embodiments, the conductive member (e.g., the conductive first portion **621** in FIG. **19A**) may be overlapped with the antenna when viewed in a direction substantially perpendicular to a surface of the printed circuit board facing the lateral portion.

(192) According to various embodiments, the conductive member may be extended into the housing to support a lower surface of the antenna module (e.g., the PCB **590** including the array antenna **AR1** in FIG. **18**).

(193) While the disclosure has been particularly shown and described with reference to various embodiments thereof, it will be understood by those skilled in the art that various changes in form and details may be made therein without departing from the scope of the subject matter as defined by the appended claims.

(194) While the disclosure has been shown and described with reference to various embodiments thereof, it will be understood by those skilled in the art that various changes in form and details may be made therein without departing from the spirit and scope of the disclosure as defined by the appended claims and their equivalents.

Claims

1. A portable communication device comprising: a housing comprising a rear cover and a lateral member forming a rear surface and a lateral surface of the portable communication device, respectively; and an antenna structure disposed along a portion of the lateral surface such that the antenna structure is configured to radiate a radio signal through the lateral surface, wherein the lateral member comprises a non-conductive portion extended along the lateral surface as covering an entire length of the antenna structure, wherein the lateral member further comprises a conductive portion having a concave surface facing a first ending portion of the non-conductive portion in a length direction thereof, wherein the concave surface is in contact with the non-conductive portion at a position not overlapped with the antenna structure when the lateral surface is viewed from an outside of the portable communication device, and wherein a region of the non-conductive portion facing the concave surface is positioned near one of right or left ends of the antenna structure when the lateral surface is viewed from the outside of the portable communication device.
2. The portable communication device of claim 1, wherein the non-conductive portion is disposed substantially between the conductive portion and the antenna structure.
3. The portable communication device of claim 1, wherein the lateral member further includes another conductive portion having a concave surface facing another ending portion of the non-conductive portion opposite to the first ending portion.
4. The portable communication device of claim 3, wherein a distance (**D1**) between the concave surface of the conductive portion and the concave surface of the other conductive portion is longer than a length (**D2**) of the antenna surface.
5. The portable communication device of claim 1, further comprising: a front cover; a display comprising: a display panel disposed between the front cover and the rear cover and overlapping at least one opening; and a conductive sheet disposed on a rear surface of the display panel so as not to overlap the at least one opening.
6. The portable communication device of claim 5, wherein the conductive sheet comprises at least one notch or slot, the at least one notch or slot being formed in a region overlapping the at least one opening.
7. The portable communication device of claim 5, further comprising a conductive connection member disposed between the conductive sheet and the conductive portion.
8. The portable communication device of claim 7, wherein the conductive connection member comprises a metal member configured to electrically connect the conductive portion and the

conductive sheet.

9. The portable communication device of claim 7, wherein the conductive connection member further comprises an electrical connecting position disposed between the conductive portion and the conductive sheet and configured to determine radiation characteristics of the antenna structure.

10. An electronic device comprising: a front cover and a rear cover forming a part of an outer appearance of the electronic device; an antenna structure comprising a plurality of antenna elements disposed between the front cover and the rear cover; and a support member disposed between the front cover and the rear cover, wherein the rear cover and a lateral member forming a rear surface and a lateral surface of the electronic device, respectively, wherein the antenna structure is disposed along a portion of the lateral surface such that the antenna structure is configured to radiate a radio signal through the lateral surface, wherein the lateral member comprises a non-conductive portion extends along the lateral surface as covering an entire length of the antenna structure, wherein the lateral member further comprises a conductive portion having a concave surface facing a first ending portion of the non-conductive portion in a length direction thereof, wherein the concave surface is in contact with the non-conductive portion at a position not overlapped with the antenna structure when the lateral surface is viewed from an outside of the electronic device, and wherein a region of the non-conductive portion facing the concave surface is positioned near one of right or left ends of the antenna structure when the lateral surface is viewed from the outside of the electronic device.

11. The electronic device of claim 10, wherein the non-conductive portion is disposed substantially between the conductive portion and the antenna structure.

12. The electronic device of claim 10, wherein the lateral member further includes another conductive portion having a concave surface facing another ending portion of the non-conductive portion opposite to the first ending portion.

13. The electronic device of claim 12, wherein a distance (D1) between the concave surface of the conductive portion and the concave surface of the other conductive portion is longer than a length (D2) of the antenna surface.

14. The electronic device of claim 10, further comprising: a front cover; a display comprising: a display panel disposed between the front cover and the rear cover and overlapping at least one opening; and a conductive sheet disposed on a rear surface of the display panel so as not to overlap the at least one opening.

15. The electronic device of claim 14, wherein the conductive sheet comprises at least one notch or slot, the at least one notch or slot being formed in a region overlapping the at least one opening.

16. The electronic device of claim 14, wherein the electronic device further comprises a conductive connection member disposed between the conductive sheet and the conductive portion.

17. The electronic device of claim 16, wherein the conductive connection member comprises a metal member configured to electrically connect the conductive portion and the conductive sheet.

18. The electronic device of claim 16, wherein the conductive connection member further comprises an electrical connecting position disposed between the conductive portion and the conductive sheet and configured to determine radiation characteristics of the antenna structure.

19. A portable communication device comprising: a housing comprising a rear cover and a lateral member forming a rear surface and a lateral surface of the portable communication device, respectively; and an antenna structure disposed along a portion of the lateral surface such that an antenna surface of the antenna structure via which a radio signal is radiated faces the portion of the lateral surface, wherein the lateral member comprises a non-conductive portion extended along the lateral surface as covering an entire length of the antenna structure, wherein the lateral member further comprises a conductive portion having a concave surface facing a first ending portion of the non-conductive portion in a length direction thereof, wherein the concave surface is in contact with the non-conductive portion at a position not overlapped with the antenna structure when the lateral

surface is viewed from an outside of the portable communication device, and wherein one of the antenna structure's lengthwise edges faces the lateral member and the non-conductive portion.
