

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12401387
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Lu; Shih-Wen et al.

Electronic module

Abstract

The present disclosure provides an electronic module including a circuit including a transmitting part and a receiving part physically separated from the transmitting part. The electronic module also includes an element isolated from the circuit and configured to block electrical interference between the transmitting part and the receiving part.

Inventors: Lu; Shih-Wen (Kaohsiung, TW), Chen; Chun-Jen (Kaohsiung, TW), Tseng; Po-Hsiang (Kaohsiung, TW), Lin; Hsin-Han (Kaohsiung, TW), Yu; Ming-Lun (Kaohsiung, TW)

Applicant: Advanced Semiconductor Engineering, Inc. (Kaohsiung, TW)

Family ID: 1000008778543

Assignee: ADVANCED SEMICONDUCTOR ENGINEERING, INC. (Kaohsiung, TW)

Appl. No.: 18/414372

Filed: January 16, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240154642 A1	May. 09, 2024

Related U.S. Application Data

continuation parent-doc US 17407067 20210819 US 11876551 child-doc US 18414372

Publication Classification

Int. Cl.: H04B1/525 (20150101); H04B1/04 (20060101); H04B1/10 (20060101); H04B1/48 (20060101)

U.S. Cl.:

CPC **H04B1/525** (20130101); **H04B1/0475** (20130101); **H04B1/1009** (20130101); **H04B1/48** (20130101); H04B2001/485 (20130101)

Field of Classification Search

CPC: H04B (1/0475); H04B (1/1009); H04B (1/48); H04B (1/525); H04B (2001/485)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
6472952	12/2001	Sakai et al.	N/A	N/A
11658514	12/2022	Mohanty	600/302	A61N 5/045
11876551	12/2023	Lu	N/A	H04B 1/1009
2005/0136850	12/2004	Arai	N/A	N/A
2013/0043961	12/2012	Gebauer et al.	N/A	N/A
2016/0142041	12/2015	Kuwahara	333/195	H03H 9/1085
2016/0381687	12/2015	Yang	370/281	H03H 7/40
2019/0029109	12/2018	Uejima	N/A	N/A
2021/0075093	12/2020	Zhang	N/A	C08K 7/14
2021/0152195	12/2020	Uejima	N/A	N/A
2021/0234526	12/2020	Kim	N/A	H04B 1/40
2021/0239754	12/2020	Schat	N/A	G01R 31/2822

OTHER PUBLICATIONS

Final Office Action for U.S. Appl. No. 17/407,067, issued Jul. 20, 2023, 9 pages. cited by applicant
Non-Final Office Action for U.S. Appl. No. 17/407,067, issued Feb. 1, 20223, 10 pages. cited by applicant
Notice of Allowance for U.S. Appl. No. 17/407,067, issued Sep. 6, 2023, 5 pages. cited by applicant

Primary Examiner: Vo; Nguyen T

Attorney, Agent or Firm: FOLEY & LARDNER LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION (1) This application is a continuation of U.S. patent application Ser. No. 17/407,067, filed Aug. 19, 2021, the content of which is incorporated herein by reference in its entirety.

BACKGROUND

1. Technical Field

(1) The present disclosure relates generally to an electronic module, and more particularly to an electronic module used in wireless communications.

2. Description of the Related Art

(2) In full-duplex communication technology, duplexing devices are commonly used in wireless communication equipment to allow multi-directional signal communication over a single path at any given time. The duplexing device isolates the transmitting part (TX) and the receiving part (RX) and allows the TX and RX to use the same antenna.

(3) As wireless communication equipment becomes more compact (or when more devices are incorporated in a same wireless communication equipment), the TX and RX may be disposed in close proximity. Undesirable interference when operating the TX and RX simultaneously presents a problem.

SUMMARY

(4) In some arrangements, an electronic module includes a circuit including a transmitting part and a receiving part physically separated from the transmitting part. The electronic module also includes an element isolated from the circuit and configured to block electrical interference between the transmitting part and the receiving part.

(5) In some arrangements, an electronic module includes a supporting element including a first surface and a second surface opposite to the first surface. The electronic module also includes a transmitting part supported by the first surface of the supporting element and a receiving part supported by the second surface of the supporting element. The electronic module also includes an antenna part adjacent to the receiving part and configured to receive a first signal from the transmitting part and configured to transmit a second signal to the receiving part.

(6) In some arrangements, an electronic module includes a first carrier, a second carrier physically separated from the first carrier, and a duplexing device including a transmitting part adjacent to the first carrier and a receiving part adjacent to the second carrier.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Aspects of the present disclosure are readily understood from the following detailed description when read with the accompanying figures. It should be noted that various features may not be drawn to scale. The dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.

(2) FIG. 1 illustrates a cross-sectional view of an electronic module in accordance with some arrangements of the present disclosure.

(3) FIG. 2 illustrates a functional block diagram of an electronic module in accordance with some arrangements of the present disclosure.

(4) FIG. 3 illustrates a cross-sectional view of an electronic module in accordance with some arrangements of the present disclosure.

(5) FIG. 4 illustrates a top view of an electronic module in accordance with some arrangements of the present disclosure.

(6) FIG. 5 illustrates a top view of an electronic module in accordance with some arrangements of the present disclosure.

(7) FIG. 6 illustrates a top view of an electronic module in accordance with some arrangements of the present disclosure.

(8) FIG. 7 illustrates a top view of an electronic module in accordance with some arrangements of the present disclosure.

(9) FIG. 8 illustrates a cross-sectional view of an electronic module in accordance with some arrangements of the present disclosure.

(10) Common reference numerals are used throughout the drawings and the detailed description to indicate the same or similar elements. The present disclosure will be more apparent from the following detailed description taken in conjunction with the accompanying drawings.

DETAILED DESCRIPTION

(11) The following disclosure provides many different arrangements, or examples, for implementing different features of the provided subject matter. Specific examples of components and arrangements are described below. These are, of course, merely examples and are not intended to be limiting. In the present disclosure, reference to the formation of a first feature over or on a second feature in the description that follows may include arrangements in which the first and second features are formed in direct contact, and may also include arrangements in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. Besides, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for simplicity and clarity and does not in itself dictate a relationship between the various arrangements and/or configurations discussed.

(12) Arrangements of the present disclosure are discussed in detail below. It should be appreciated, however, that the present disclosure provides many applicable concepts that can be embodied in a wide variety of specific contexts. The specific arrangements discussed are merely illustrative and do not limit the scope of the disclosure.

(13) FIG. 1 illustrates a cross-sectional view of an electronic module **1** in accordance with some arrangements of the present disclosure. In some arrangements, the electronic module **1** may be or include a duplexing device used in wireless communications. In some arrangements, the electronic module **1** may include a substrate **10**, a receiving part **11**, a transmitting part **12**, an antenna part **13**, a shielding structure **14**, a controlling device **15**, and encapsulants **16**, **16'**. In some arrangements, the electronic module **1** may include a semiconductor device or a semiconductor device package.

(14) In some arrangements, the substrate **10** may be or include, for example, a printed circuit board (PCB) (such as a paper-based copper foil laminate), a composite copper foil laminate, a polymer-impregnated glass-fiber-based copper foil laminate, or so on. The substrate **10** may have a surface **101** and a surface **102** opposite to the surface **101**. In some arrangements, the substrate **10** may include a redistribution layer (RDL), a grounding element, a feeding line, a conductive transmission line, or other conductive structures. In some arrangements, the substrate **10** may include an electrical contact **10e** on the surface **102** for providing electrical connections between the electronic module **1** and an external device (e.g., a PCB, an electronic device, another electronic module, and so on). The electrical contact **10e** may include a solder ball, such as a controlled collapse chip connection (C4) bump, a ball grid array (BGA) or a land grid array (LGA). In some arrangements, the substrate **10** may include one or more supporting elements or one or more carrier configured to support the receiving part **11**, the transmitting part **12**, and the antenna part **13**.

(15) In some arrangements, each of the receiving part **11**, the transmitting part **12**, and the antenna part **13** may be a chip or a die including a semiconductor substrate, one or more integrated circuit devices, and one or more overlying interconnection structures therein. The integrated circuit devices may include active devices such as transistors and/or passive devices such as resistors, capacitors, inductors, or a combination thereof.

(16) In some arrangements, each of the receiving part **11**, the transmitting part **12**, and the antenna part **13** may be a path or a port. In some arrangements, the receiving part **11** may be connected with a receiver or a receiving part of a transceiver (such as the receiving part RX of the transceiver **21** in FIG. 2). In some arrangements, the transmitting part **12** may be connected with a transmitter or a transmitting part of a transceiver (such as the transmitting part TX of the transceiver **21** in FIG. 2). In some arrangements, the antenna part **13** may be connected with an antenna (such as the antenna **22** in FIG. 2).

(17) In some arrangements, one or more of the receiving part **11**, the transmitting part **12**, and the antenna part **13** may be partially embedded in the substrate **10**. In some arrangements, one or more of the receiving part **11**, the transmitting part **12**, and the antenna part **13** may be partially exposed from the substrate **10** as shown. In other arrangements, one or more of the receiving part **11**, the

transmitting part **12**, and the antenna part **13** may be entirely embedded in the substrate **10**, such that no part of one or more of the receiving part **11**, the transmitting part **12**, and the antenna part **13** is exposed from the substrate **10**.

(18) In some arrangements, the receiving part **11** may be disposed on the surface **101** of the substrate **10**. In some arrangements, the receiving part **11** may be adjacent to the surface **101** of the substrate **10**. In some arrangements, the receiving part **11** and the transmitting part **12** may be disposed on opposite sides of the substrate **10**. For example, the transmitting part **12** may be disposed on the surface **102** of the substrate **10**. For example, the transmitting part **12** may be adjacent to the surface **102** of the substrate **10**. In some arrangements, the receiving part **11** and the transmitting part **12** may be physically spaced apart with a gap therebetween. In some arrangements, the receiving part **11** may be physically separated from the transmitting part **12**. For example, the receiving part **11** and the transmitting part **12** may be separated by the substrate **10** as shown. In other arrangements, the receiving part **11** and the transmitting part **12** may be disposed on the same side of the substrate **10** (for example, as described in FIGS. 4, 5, 6, and 7). For example, the receiving part **11** and the transmitting part **12** may be disposed side-by-side on the surface **101** or the surface **102**. In the arrangements in which the receiving part **11** and the transmitting part **12** are disposed on the same side of the substrate **10**, the receiving part **11** may be physically separated from and spaced apart with the transmitting part **12** with a gap therebetween.

(19) In some arrangements, the antenna part **13** and the receiving part **11** may be disposed on the same side of the substrate **10**. For example, the antenna part **13** may be disposed on the surface **101** of the substrate **10**. In some arrangements, the antenna part **13** and the receiving part **11** may be integrated. For example, the antenna part **13** and the receiving part **11** may be integrated on the surface **101** of the substrate **10**. For example, the antenna part **13** and the receiving part **11** may be integrated on the same carrier. For example, as shown in FIG. 5, the antenna part **13** and the receiving part **11** may be integrated on (e.g., embedded in, contacting, coupled to, attached to, and so on) the same carrier **11a**. The carrier **11a** may be a part of the substrate **10** or may be a carrier physically separated from the substrate **10**.

(20) In some arrangements, the receiving part **11**, the transmitting part **12**, and the antenna part **13** may be electrically connected through the substrate **10**. For example, the receiving part **11**, the transmitting part **12**, and the antenna part **13** may be electrically connected through a conductive transmission line (not shown), such as a microstrip line in the substrate **10**.

(21) In some arrangements, the receiving part **11** and the transmitting part **12** may be configured to conduct electronic signals having a substantially same frequency and/or bandwidth. In some arrangements, the receiving part **11** and the transmitting part **12** may be configured to conduct electronic signals having different frequencies or bandwidths. In some arrangements, the transmitting part **12** and the receiving part **11** may use the same antenna part **13**. For example, wireless transmission and the reception of the electromagnetic waves may be performed through the same antenna part **13**.

(22) In some arrangements, the shielding structure **14** may be disposed between the receiving part **11** and the transmitting part **12**. In some arrangements, the shielding structure **14** may extend in a direction substantially parallel to the surface **101** and/or the surface **102** of the substrate **10**. In some arrangements, the shielding structure **14** may be stacked on the transmitting part **12**. In some arrangements, the receiving part **11** may be stacked on the shielding structure **14**. In some arrangements, the shielding structure **14** may be configured to prevent electromagnetic interference (EMI) between the receiving part **11** and the transmitting part **12**. In some arrangements, the shielding structure **14** may be configured to block electrical interference between the receiving part **11** and the transmitting part **12**. In some arrangements, the shielding structure **14** may be disposed within the substrate **10** as shown. In some arrangements, the shielding structure **14** may include a grounding element or a grounding layer in the substrate **10**. For example, the grounding layer in the substrate **10** may function to prevent EMI and block electrical interference between the receiving

part **11** and the transmitting part **12**. In some arrangements, the shielding structure **14** may include be any number of grounding layer in the substrate **10**. In some arrangements, the shielding structure **14** may include an element isolated from the receiving part **11** and the transmitting part **12**. In other words, the shielding structure **14** may be not electrically connected to either the receiving part **11** or the transmitting part **12**.

(23) In some arrangements, the controlling device **15** may be disposed on the surface **101** of the substrate **10**. In some other arrangements, the controlling device **15** may be disposed on the surface **102** of the substrate **10**. In some other arrangements, the controlling device **15** may be disposed outside of the electronic module **1** (as shown in FIG. **8**).

(24) In some arrangements, the controlling device **15** may be electrically connected to the substrate **10** (e.g., to the conductive structures thereof) by flip-chip or wire-bonding. In some arrangements, the controlling device **15** may be electrically connected to the receiving part **11** through the substrate **10**. For example, the controlling device **15** may be electrically connected to the receiving part **11** through a conductive transmission line, such as a microstrip line in the substrate **10**. In some arrangements, the controlling device **15** may be electrically connected to the transmitting part **12** through the substrate **10**. For example, the controlling device **15** may be electrically connected to the transmitting part **12** through a conductive transmission line, such as a microstrip line in the substrate **10**.

(25) In some arrangements, the controlling device **15** may be a chip or a die including a semiconductor substrate, one or more integrated circuit devices and one or more overlying interconnection structures therein. The integrated circuit devices may include active devices such as transistors and/or passive devices such as resistors, capacitors, inductors, or a combination thereof. In some arrangements, the controlling device **15** may be configured to control the conduction of the electronic signals of the transmitting part **12** and the receiving part **11**, further described in FIG. **2**.

(26) In some arrangements, the encapsulant **16** may be disposed on the surface **101** of the substrate **10** and covers or surrounds the components located on or adjacent to the surface **101** of the substrate **10**, including the receiving part **11**, the antenna part **13**, and the controlling device **15** as shown. In some arrangements, the encapsulant **16'** may be disposed on the surface **102** of the substrate **10** and covers or surrounds the components located on or adjacent to the surface **102**, including the transmitting part **12** as shown. In some arrangements, the encapsulant **16** and/or the encapsulant **16'** may be physically isolated from the shielding structure **14**. For example, the encapsulant **16** and/or the encapsulant **16'** may be physically isolated or separate from the shielding structure **14** by the substrate **10**, such that the substrate **10** is between the shielding structure **14** and the encapsulants **16** and/or **16'**. In some arrangements, the antenna part **13** may be at least partially exposed from the encapsulant **16**. In some arrangements, the electrical contact **10e** may be at least partially exposed from the encapsulant **16'**. In an example, as shown, the electrical contact **10e** is exposed in a concave space defined by the encapsulant **16'**. In other arrangements, the encapsulant **16** and/or the encapsulant **16'** may be omitted.

(27) In some arrangements, each of the encapsulant **16** and the encapsulant **16'** may include an epoxy resin having fillers, a molding compound (e.g., an epoxy molding compound or other molding compound), a polyimide, a phenolic compound or material, a material with a silicone dispersed therein, or a combination thereof.

(28) FIG. **2** illustrates a functional block diagram of an electronic module in accordance with some arrangements of the present disclosure. In some arrangements, the function of the electronic module **1** in FIG. **1** may be a part of the functional block diagram in FIG. **2**. The functional block diagram may include a duplexing device **20**, a transceiver **21**, an antenna **22**, and a controlling device **23**. In some arrangements, an example of the duplexing device **20** is the electronic module **1** in FIG. **1**.

(29) The transceiver **21** may have a transmitting part TX connected to a port (such as the

transmitting part **12** of the electronic module **1**) of the duplexing device **20** through a power amplifier (PA) **24**. In some arrangements, the transmitting part TX may be configured to output an electronic signal (such as a transmission signal) to the duplexing device **20**. The electronic signal may be conducted through the PA **24** and a transmission path (such as the transmitting part **12** of the electronic module **1**). The transceiver **21** may have a receiving part RX connected to a port (such as the receiving part **11** of the electronic module **1**) of the duplexing device **20** through a low-noise amplifier (LNA) **25**. In some arrangements, the receiving part RX may be configured to receive an electronic signal (such as a reception signal) from the duplexing device **20**. The electronic signal may be conducted through a reception path (such as the receiving part **11** of the electronic module **1**) and the LNA **25**. In some arrangements, the electronic signals in the transmission path and the reception path may have a substantially same frequency and/or bandwidth. In some arrangements, the electronic signals in the transmission path and the reception path may have different frequencies and/or bandwidths. In some arrangements, the transceiver **21** may include a combination of a transmitter and a receiver. In some arrangements, the transceiver **21** may include a transmitter and a receiver physically separated from each other.

(30) The antenna **22** may be connected to a port (such as the antenna part **13**) of the duplexing device **20**. In some arrangements, the antenna **22** may include a patch antenna, a chip antenna, an inverted-F antennas, or so on. In some arrangements, the antenna **22** may be configured to emit a transmission signal from the transmitting part TX in the form of electromagnetic waves and catch or require a desired reception signal out of electromagnetic waves. The receiving part RX and the transmitting part TX of the transceiver **21** may not directly connect to the antenna **22**. The receiving part RX and the transmitting part TX of the transceiver **21** may connect to the antenna **22** through the duplexing device **20**. In other words, the receiving part RX and the transmitting part TX may connect to the antenna **22** through a circuit including the receiving part **11**, the transmitting part **12**, and the antenna part **13** in FIG. **1**. The receiving part RX and the transmitting part TX may use the same antenna **22**. For example, the transmission and the reception of the electromagnetic waves may be conducted through the same antenna **22**.

(31) The controlling device **23** may connect to each of the duplexing device **20**, the transceiver **21**, and the antenna **22**. In some arrangements, the controlling device **23** may be configured to control the duplexing device **20**. For example, the controlling device **23** may generate a control signal to control the duplexing device **20**. In some arrangements, the controlling device **23** may be configured to control the transmission and the reception of the electromagnetic waves.

(32) The duplexing device **20** may have three ports connected with the transmitting part TX, the receiving part RX, and the antenna **22**. In some arrangements, the duplexing device **20** may be the circuit between the transmitting part TX, the receiving part RX, and the antenna **22**. In some arrangements, the duplexing device **20** may be responsive to a control signal generated from the controlling device **23**.

(33) In some arrangements, the electronic signals from the PA **24** to the antenna **22** through the duplexing device **20** (such as through the transmitting part **12** of the electronic module **1** in FIG. **1**) and the electronic signals from the antenna **22** to the LNA **25** through the duplexing device **20** (such as through the receiving part **11** of the electronic module **1** in FIG. **1**) may be substantially conducted at the same time without interfering with each other. In some arrangements, the duplexing device **20** may be configured to allow multi-directional signal communication (e.g., for transmission and reception) over a single path. For example, in the duplexing device **20**, a first path is configured to conduct a first electronic signal from the transmitting part TX to the antenna **22** and a second path is configured to conduct a second electronic signal from the antenna **22** to the receiving part RX. In some arrangements, the first signal and the second signal may be conducted at the same time. In some arrangements, the frequency of the first signal and the frequency of the second signal may be substantially the same. In some arrangements, the duplexing device **20** may be configured to perform a full duplex operation. In some arrangements, the duplexing device **20**

may include a circulator. In some arrangements, the duplexing device **20** may have a circuit that functions as a circulator.

(34) For example, the controlling device **23** may be configured to generate a control signal to control the duplexing device **20** to allow multi-directional signal communication over a single path. For example, the controlling device **23** may be configured to generate a control signal to control the duplexing device **20** to perform a full duplex operation. For example, the controlling device **23** may be configured to generate a control signal to control the duplexing device **20** to function as a circulator.

(35) For example, the controlling device **23** may be configured to provide a single path from the transmitting part TX to the antenna **22** through the duplexing device **20**.

(36) For example, the controlling device **23** may be configured to provide a single path from the receiving part RX to the transmitting part TX through the duplexing device **20**.

(37) For example, the controlling device **23** may be configured to prevent a direct path from the transmitting part TX to the receiving part RX through the duplexing device **20**.

(38) For example, the controlling device **23** may be configured to control the duplexing device **20** to route signals from the transmitting part TX to the antenna **22** and from the antenna **22** to the receiving part RX, without allowing signals to pass directly from the transmitting part TX to the receiving part RX.

(39) In some other arrangements, the controlling device **23** may be omitted. For example, the electronic signals from the PA **24** to the antenna **22** through the duplexing device **20** and the electronic signals from the antenna **22** to the LNA **25** through the duplexing device **20** may be substantially conducted at the same time without interfering with each other with or without the controlling device **23**. For example, the duplexing device **20** may be configured to allow multi-directional signal communication (e.g., for transmission and reception) over a single path with or without the controlling device **23**.

(40) In an example, to enhance degree of isolation between the transmitting part TX and the receiving part RX, a circulator may be inserted, such as between the PA **24** and the duplexing device **20**. However, such an additional circulator may increase the weight and the cost and may further increase insertion loss from the transmitting part TX to the antenna **22** and/or from the antenna **22** to the receiving part RX.

(41) According to some arrangements of the present disclosure, the transmitting part and the receiving part of the duplexing device **200** are integrated in (e.g., embedded in, contacting, coupled to, attached to, and so on) an electronic module and isolated by a shielding structure. For example, in FIG. 1, the transmitting part **12** and the receiving part **11** are integrated in the electronic module **1** and are isolated by the shielding structure **14**. The package size of the electronic module **1** may be reduced.

(42) The degree of isolation between the transmitting part TX and the receiving part RX (e.g., the transmitting part **12** and the receiving part **11**) may be enhanced. For example, self-interference in full-duplex communication may be alleviated or eliminated. In addition, the shielding structure (e.g., the shielding structure **14**) provides simpler and cheaper isolation than the addition of another circulator. Low insertion loss from the transmitting part TX of the transceiver **21** to the antenna **22** and/or from the antenna **22** to the receiving part RX of the transceiver **21** may be achieved while providing high isolation from the transmitting part TX to the receiving part RX.

(43) FIG. 3 illustrates a cross-sectional view of an electronic module **3** in accordance with some arrangements of the present disclosure. The electronic module **3** of FIG. 3 is similar to the electronic module **1** of FIG. 1, and the differences therebetween are described below.

(44) In some arrangements, as shown in FIG. 3, the receiving part **11** may be disposed on or adjacent to the surface **102** of the substrate **10** and the transmitting part **12** may be disposed on or adjacent to the surface **101** of the substrate **10**.

(45) In some arrangements, the antenna part **13** may be disposed on or adjacent to the surface **101**

of the substrate **10**. In some arrangements, the antenna part **13** and the transmitting part **12** may be disposed on the same side of the substrate **10**. In some arrangements, the antenna part **13** and the transmitting part **12** may be integrated. For example, the antenna part **13** and the transmitting part **12** may be integrated on the surface **101** of the substrate **10**. For example, the antenna part **13** and the transmitting part **12** may be integrated on (e.g., embedded in, contacting, coupled to, attached to, and so on) the same carrier. For example, as shown in FIG. 7, the antenna part **13** and the transmitting part **12** may be integrated on the same carrier **12a**. The carrier **12a** may be a part of the substrate **10** or may be a carrier physically separated from the substrate **10**.

(46) FIG. 4 illustrates a top view of an electronic module in accordance with some arrangements of the present disclosure. In some arrangements, FIG. 4 illustrates a relative locations among the elements in the electronic module **1** of FIG. 1.

(47) In FIG. 4, the receiving part **11** may be disposed on a carrier **11a**, the transmitting part **12** may be disposed on a carrier **12a**, and the antenna part **13** may be disposed on a carrier **13a**. In some arrangements, the carrier **11a**, the carrier **12a**, and the carrier **13a** may be physically spaced apart from one another with a gap therebetween. In some arrangements, the shielding structure **14** may be disposed between the carrier **11a** and the carrier **12a**.

(48) In some arrangements, the carrier **11a** may not directly contact the carrier **12a**. In some arrangements, the carrier **11a** may not indirectly contact the carrier **12a**. In some arrangements, the carrier **11a** may be spaced apart from the carrier **12a**. In some arrangements, the carrier **11a** may be adjacent to the carrier **12a**. In some arrangements, a surface of the carrier **11a** on which the receiving part **11** is disposed may be adjacent to a surface of the carrier **12a** on which the transmitting part **12** is disposed.

(49) In some arrangements, the distance “D1” between the receiving part **11** and the antenna part **13** may be different from the distance “D2” between the transmitting part **12** and the antenna part **13**. For example, the distance D2 may be greater than the distance D1. For example, the distance D2 may exceed the distance D1. The distance D1 may be less than the distance D2. The distance D1 may include the shortest distance between the receiving part **11** and the antenna part **13**, the distance between two closest points of the receiving part **11** and the antenna part **13**, or the distance between the centers of the receiving part **11** and the antenna part **13**. The distance D2 may include the shortest distance between the transmitting part **12** and the antenna part **13**, the distance between two closest points of the transmitting part **12** and the antenna part **13**, or the distance between the centers of the transmitting part **12** and the antenna part **13**. In some arrangements, since electromagnetic waves attenuated when passing through mediums (such as air), the energy of the electromagnetic waves received by the antenna (such as the antenna **22** in FIG. 2) may be weak. In some arrangements, by arranging the antenna part **13** close to the receiving part **11**, signal loss between the antenna (such as the antenna **22** in FIG. 2) and the receiving part **11** may be alleviated. On the other hand, the transmitting part **12** is configured to conduct electronic signals which is amplified (such as by the PA in FIG. 2), the signal loss between the transmitting part **12** and the antenna part **13** is not as severe as the signal loss between the receiving part **11** and the antenna part **13** is.

(50) In some arrangements, the surface of the carrier **11a** on which the receiving part **11** is disposed and the surface of the carrier **12a** on which the transmitting part **12** is disposed may face the same direction. For example, the carrier **11a** and the carrier **12a** may be disposed on the same side of the carrier **11a** and the carrier **12a**. For example, the surface of the carrier **11a** on which the receiving part **11** is disposed and the surface of the carrier **12a** on which the transmitting part **12** is disposed may be parallel.

(51) In other arrangements, the surface of the carrier **11a** on which the receiving part **11** is disposed and the surface of the carrier **12a** on which the transmitting part **12** is disposed may face different directions. For example, the carrier **11a** and the carrier **12a** may be disposed on different sides of the carrier **11a** and the carrier **12a**. For example, the surface of the carrier **11a** on which the

receiving part **11** is disposed may be angled with or non-parallel to the surface of the carrier **12a** on which the transmitting part **12** is disposed.

(52) In some arrangements, the carrier **11a** may be a part of the substrate **10** in FIG. **1** or may be a carrier physically separated from the substrate **10**. In some arrangements, the carrier **12a** may be a part of the substrate **10** in FIG. **1** or may be a carrier physically separated from the substrate **10**. In some arrangements, the carrier **13a** may be a part of the substrate **10** in FIG. **1** or may be a carrier physically separated from the substrate **10**. In some arrangements, the carrier **11a** and the carrier **12a** may be at different circuit layers or different dielectric layers in the substrate **10**. For example, the carrier **11a** and the carrier **12a** may be at different elevations with respect to the surface **102** in the substrate **10**. For example, in FIG. **3**, the carrier **11a** may be or may be at a dielectric layer closer to the surface **102** and the carrier **12a** may be or may be at a dielectric layer closer to the surface **101**.

(53) FIG. **5** illustrates a top view of an electronic module in accordance with some arrangements of the present disclosure. In some arrangements, FIG. **5** illustrates a relative locations among the elements in the electronic module **1** of FIG. **1**. The top view of FIG. **5** is similar to the top view of FIG. **4**, and the differences therebetween are described below.

(54) In FIG. **5**, the receiving part **11** and the antenna part **13** may be integrated in (e.g., embedded in, contacting, coupled to, attached to, and so on) the same carrier **11a**, and the carrier **13a** in FIG. **4** is omitted. The carrier **11a** may be a part of the substrate **10** in FIG. **1** or may be a carrier physically separated from the substrate **10**.

(55) FIG. **6** illustrates a top view of an electronic module in accordance with some arrangements of the present disclosure. In some arrangements, FIG. **6** illustrates a relative locations among the elements in the electronic module **1** of FIG. **1**. The top view of FIG. **6** is similar to the top view of FIG. **4**, and the differences therebetween are described below.

(56) In FIG. **6**, the distance **D1'** between the receiving part **11** and the antenna part **13** is greater than the distance **D2'** between the transmitting part **12** and the antenna part **13**. For example, the distance **D1'** may exceed the distance **D2'**. The distance **D2'** may be less than the distance **D1'**. The distance **D1'** may include the shortest distance between the receiving part **11** and the antenna part **13**, the distance between two closest points of the receiving part **11** and the antenna part **13**, or the distance between the centers of the receiving part **11** and the antenna part **13**. The distance **D2'** may include the shortest distance between the transmitting part **12** and the antenna part **13**, the distance between two closest points of the transmitting part **12** and the antenna part **13**, or the distance between the centers of the transmitting part **12** and the antenna part **13**.

(57) FIG. **7** illustrates a top view of an electronic module in accordance with some arrangements of the present disclosure. In some arrangements, FIG. **7** illustrates a relative locations among the elements in the electronic module **1** of FIG. **1**. The top view of FIG. **7** is similar to the top view of FIG. **4**, and the differences therebetween are described below.

(58) In FIG. **7**, the transmitting part **12** and the antenna part **13** may be integrated in the same carrier **12a**, and the carrier **13a** in FIG. **4** is omitted. The carrier **12a** may be a part of the substrate **10** in FIG. **1** or may be a carrier physically separated from the substrate **10**.

(59) FIG. **8** illustrates a cross-sectional view of an electronic module **8** in accordance with some arrangements of the present disclosure. The electronic module **8** of FIG. **8** is similar to the electronic module **1** of FIG. **1**, and the differences therebetween are described below.

(60) The electronic module **8** may include the electronic module **1** in FIG. **1**, a substrate **80**, and a circuit region **81**.

(61) The electronic module **1** and the circuit region **81** may be disposed on the substrate **80**. The electronic module **1** and the circuit region **81** may be physically separated with a gap (filled by the substrate **80**) therebetween. The electronic module **1** and the circuit region **81** may be electrically connected through the substrate **80**.

(62) In some arrangements, the circuit region **81** may include the controlling device **15** in FIG. **1**.

In some arrangements, the circuit region **81** may include the LNA **25** and/or the PA **24** in FIG. 2. In some arrangements, the circuit region **81** may include the transceiver **21** in FIG. 2. In some arrangements, the circuit region **81** may include the controlling device **22** in FIG. 2. In some arrangements, the circuit region **81** may include the controlling device **23** in FIG. 2.

(63) Spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper,” “left,” “right” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation, in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly. It should be understood that when an element is referred to as being “connected to” or “coupled to” another element, it may be directly connected to or coupled to the other element, or intervening elements may be present.

(64) As used herein, the terms “approximately”, “substantially”, “substantial” and “about” are used to describe and account for small variations. When used in conjunction with an event or circumstance, the terms can refer to instances in which the event or circumstance occurs precisely as well as instances in which the event or circumstance occurs to a close approximation. As used herein with respect to a given value or range, the term “about” generally means within $\pm 10\%$, $\pm 5\%$, $\pm 1\%$, or $\pm 0.5\%$ of the given value or range. Ranges can be expressed herein as from one endpoint to another endpoint or between two endpoints. All ranges disclosed herein are inclusive of the endpoints unless specified otherwise. The term “substantially coplanar” can refer to two surfaces within micrometers (μm) of lying along the same plane, such as within 10 within 5 within 1 or within $0.5\ \mu\text{m}$ of lying along the same plane. When referring to numerical values or characteristics as “substantially” the same, the term can refer to the values lying within $\pm 10\%$, $\pm 5\%$, $\pm 1\%$, or $\pm 0.5\%$ of an average of the values.

(65) The foregoing outlines features of several arrangements and detailed aspects of the present disclosure. The arrangements described in the present disclosure may be readily used as a basis for designing or modifying other processes and structures for carrying out the same or similar purposes and/or achieving the same or similar advantages of the arrangements introduced herein. Such equivalent constructions do not depart from the spirit and scope of the present disclosure, and various changes, substitutions, and alterations may be made without departing from the spirit and scope of the present disclosure.

Claims

1. A semiconductor device, comprising: a first carrier having a first side and a second side; a duplexing device including a transmitting part disposed adjacent to the first side and a receiving part disposed adjacent to the second side; a first encapsulant disposed over the second side of the first carrier and encapsulating the receiving part; and a controlling device disposed over the first carrier, the controlling device configured to control the duplexing device to perform a full duplex operation, wherein the controlling device is disposed closer to the receiving part than to the transmitting part.
2. The semiconductor device of claim 1, further comprising: an element configured to block electrical interference between the transmitting part and the receiving part.
3. The semiconductor device of claim 2, wherein the element is disposed within the first carrier.
4. The semiconductor device of claim 2, wherein the element comprises a grounding layer.
5. The semiconductor device of claim 2, wherein the element is overlapped with the transmitting part and the receiving part in a direction substantially perpendicular to the first side of the first carrier.
6. The semiconductor device of claim 1, further comprising: a second encapsulant disposed under

the first side of the first carrier and encapsulating the transmitting part.

7. The semiconductor device of claim 6, wherein a lateral surface of the first encapsulant, a lateral surface of the second encapsulant, and a lateral surface of the first carrier are substantially aligned.
 8. The semiconductor device of claim 6, wherein a thickness of the first encapsulant is greater than a thickness of the second encapsulant.
 9. The semiconductor device of claim 1, wherein the first side is opposite to the second side.
 10. The semiconductor device of claim 1, further comprising: a plurality of electrical contacts disposed adjacent to the first side of the first carrier and configured to connect the semiconductor device and an external device.
 11. The semiconductor device of claim 10, wherein at least one of the plurality of electrical contacts and the controlling device are at least vertically overlapped.
 12. The semiconductor device of claim 10, further comprising: a second encapsulant having a plurality of openings for accommodating the plurality of electrical contacts respectively.
 13. The semiconductor device of claim 10, wherein the transmitting part is disposed between two of the plurality of electrical contacts.
 14. The semiconductor device of claim 1, further comprising: an antenna part electrically connected to the receiving part and the transmitting part, wherein the antenna part is disposed closer to the receiving part than to the transmitting part.
 15. The semiconductor device of claim 14, wherein the antenna part is disposed closer to the second side than to the first side.
 16. The semiconductor device of claim 1, further comprising: a second carrier disposed under the first carrier; and an antenna disposed over the second carrier and beside the first carrier.
 17. The semiconductor device of claim 16, wherein the antenna is at least partially exposed from the first encapsulant.
 18. The semiconductor device of claim 17, wherein the first encapsulant is at least partially disposed between the first carrier and the receiving part of the duplexing device.
-