

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12415371
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Inomata; Toshiya

Printer

Abstract

A printer according to an embodiment includes a conveyance guide, a printing section, a position sensor, an arithmetic section, and a setting section. The conveyance guide guides an end portion in the width direction of a print medium and determines a conveyance position in the width direction of the print medium. The printing section prints on the print medium. The position sensor outputs a signal, which changes in proportion to a position in the width direction of the conveyance guide, and detects the position in the width direction of the conveyance guide. The arithmetic section creates a linear function indicating a proportional relation between the position in the width direction of the conveyance guide and the output signals. The setting section calculates the position in the width direction of the conveyance guide using the linear function and sets a printing start position in the width direction.

Inventors:	Inomata; Toshiya (Yokohama Kanagawa, JP)
Applicant:	TOSHIBA TEC KABUSHIKI KAISHA (Tokyo, JP)
Family ID:	1000008819894
Assignee:	TOSHIBA TEC KABUSHIKI KAISHA (Tokyo, JP)
Appl. No.:	18/183969
Filed:	March 15, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240308248 A1	Sep. 19, 2024

Publication Classification

Int. Cl.: B41J11/00 (20060101); B41J3/407 (20060101)

U.S. Cl.:

CPC **B41J11/0045** (20130101); **B41J3/4075** (20130101);

Field of Classification Search

CPC: B41J (11/0095); B41J (3/4075); B41J (11/42); B41J (15/04); B41J (15/042); B41J (29/38); B41J (2/01); B41J (11/0045); B41J (13/10); B41J (11/0055); B41J (13/0009); B65H (2511/24); B65H (2301/331); B65H (7/10); B65H (5/36); B65H (5/00)

USPC: 347/16; 347/19; 347/101; 347/104

References Cited

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2004-345796	12/2003	JP	N/A
2021014340	12/2020	JP	N/A

Primary Examiner: Lebron; Jannelle M

Attorney, Agent or Firm: Amin, Turocy & Watson, LLP

Background/Summary

FIELD

(1) Embodiments described herein relate generally to, for example, a printer that prints a barcode or the like on a long print medium.

BACKGROUND

(2) There has been a printer that conveys a long print medium in a longitudinal direction and prints a barcode or the like on the print medium. The printer of this type includes, for example, a pair of conveyance guides that guides both the ends of the print medium in a width direction orthogonal to a conveyance direction. The pair of conveyance guides defines a conveyance position in the width direction of the print medium and conveys the print medium at center reference. The distance between the pair of conveyance guides can be adjusted according to the width of the print medium.

(3) In contrast, there has also been a printer that puts a long print medium on one end side in the width direction of the print medium and conveys the print medium at side reference. The side-reference printer conveys the print medium with one end in the width direction of the print medium set in contact with a conveyance reference surface. Therefore, the side-reference printer includes one conveyance guide in a position opposed to the conveyance reference surface across a conveyance path for the print medium. The one conveyance guide can be adjusted, according to the width of the printing medium, in a direction separating from and coming into contact with the conveyance reference surface and guides the other end of the print medium.

(4) In the printer that conveys the print medium at the side reference, since the conveyance position of one end in the width direction of the print medium is determined by the conveyance reference surface, a printing start position in the width direction is always fixed even if a print medium having different width is set in the printer. In contrast, in the printer that conveys the print medium at the center reference, since a conveyance position of both the ends in the width direction of the

print medium changes according to the width of the print medium, a printing start position in the width direction also needs to be changed according to the width of the print medium. Therefore, in the center-reference printer, it is necessary to input the width of the print medium and set the printing start position in the width direction before a print start.

(5) In general, in the center-reference printer, after the print medium is set, the position in the width direction of the conveyance guides is adjusted according to both the ends of the print medium, and the position in the width direction of the conveyance guides after the position adjustment is detected by a sensor. The width of the print medium is determined based on a result of the detection and the printing start position in the width direction for the print medium is automatically set.

(6) However, since the center-reference printer moves the pair of conveyance guides to be separated from and brought into contact with each other, fluctuation more easily occurs in the conveyance position in the width direction of the print medium compared with the side-reference printer. If small gaps are provided between the print medium and the conveyance guides to prevent the conveyance guides from hindering conveyance of the print medium, the fluctuation in the conveyance position in the width direction of the print medium further increases. Further, the sensor that detects the position in the width direction of the conveyance guides has an individual difference. Accordingly, in the center-reference printer, it is likely that the conveyance position in the width direction of the print medium is unstable and the printing start position in the width direction greatly deviates.

Description

DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a schematic diagram illustrating a label printer according to an embodiment;
- (2) FIG. 2 is a perspective view illustrating a conveyance guide unit of the label printer illustrated in FIG. 1;
- (3) FIG. 3 is a circuit diagram of a position sensor illustrated in FIG. 2;
- (4) FIG. 4 is a diagram for explaining a procedure for attaching label paper to the label printer;
- (5) FIG. 5 is a diagram for explaining the procedure for attaching the label paper to the label printer;
- (6) FIG. 6 is a diagram for explaining the procedure for attaching the label paper to the label printer;
- (7) FIG. 7 is a diagram for explaining the procedure for attaching the label paper to the label printer;
- (8) FIG. 8 is a block diagram illustrating a control system of the label printer;
- (9) FIG. 9 is a flowchart for explaining a setting operation for a printing start position in the label printer;
- (10) FIG. 10 is a graph illustrating an example of a linear function created in ACT 2 in FIG. 9; and
- (11) FIG. 11 is a graph illustrating another example of the linear function created in ACT 2 in FIG. 9.

DETAILED DESCRIPTION

(12) A printer according to an embodiment includes a conveyance guide, a printing section, a position sensor, an arithmetic section, and a setting section. The conveyance guide is movable in a width direction orthogonal to a conveyance direction of a print medium and guides an end portion in the width direction of the print medium and determines a conveyance position in the width direction of the print medium. The printing section prints on the print medium guided by the conveyance guide and conveyed in the conveyance direction. The position sensor outputs a signal, which changes in proportion to a position in the width direction of the conveyance guide, and detects the position in the width direction of the conveyance guide. The arithmetic section creates,

based on a first output signal of the position sensor at a time when the conveyance guide is disposed in a first position in the width direction and a second output signal of the position sensor at a time when the conveyance guide is disposed in a second position different from the first position in the width direction, a linear function indicating a proportional relation between the position in the width direction of the conveyance guide and the output signals of the position sensor. The setting section calculates, from the output signals of the position sensor, the position in the width direction of the conveyance guide using the linear function created by the arithmetic section and sets, based on the calculated positions, a printing start position in the width direction by the printing section for the print medium.

(13) A label printer **100** according to an embodiment is explained below with reference to the drawings. The label printer **100** is an example of the printer described in the claims of this application. In the following explanation, in a state illustrated in FIG. **1** in which the label printer **100** is installed on a horizontal table, up-down, left-right, front-rear directions of the label printer **100** viewed from an arrow direction are defined.

(14) As illustrated in FIG. **1**, the label printer **100** includes a housing **2** and a cover **4**. The housing **2** includes a bottom wall **201**, a vertical wall **202** erected upward from the bottom wall **201**, a front wall **203** connected to the front end of the bottom wall **201** and the front end of the vertical wall **202**, and a horizontal wall **204** (FIGS. **4** to **6**) for fixing a conveyance guide unit **30** explained below. The bottom wall **201** is parallel to the table on which the label printer **100** is placed. The vertical wall **202** is erected upward from the upper surface of the bottom wall **201** and extends along a surface orthogonal to the left-right direction. The front wall **203** extends along a surface orthogonal to the front-rear direction. The horizontal wall **204** is parallel to the front wall **203** and is present in a position separated to the rear of the front wall **203**.

(15) The cover **4** is turnably connected to the upper end of the vertical wall **202** of the housing **2** via two hinges **3** including a turning shaft extended to the front and the rear. The cover **4** is turnable between an open position illustrated in FIG. **1** where a mechanism section of the label printer **100** is opened and a closed position where the mechanism section is covered. A damper **5** for smoothing an opening and closing motion of the cover **4** is present between the cover **4** and the vertical wall **202** of the housing **2**. The label printer **100** has a substantially rectangular block-like external shape in a state in which the cover **4** is closed.

(16) The front wall **203** of the housing **2** includes an operation and input section **206**, a display section **207**, and a power switch **208**. For example, the length in a width direction orthogonal to the longitudinal direction of the label paper **121** is input to the operation and input section **206** as information concerning label paper **121** (FIG. **7**) used in the label printer **100**. The operation and input section **206** is an example of the input section described in the claims of this application. The display section **207** displays information such as a position in the width direction of guide members **31** and **32** explained below and a printing start position in the width direction for the label paper **121**.

(17) The label printer **100** includes a supply shaft **6** to which a label paper roll **12** (FIG. **7**) is attached, a feeding shaft **7** to which a ribbon roll obtained by winding an ink ribbon before use in a roll shape is attached, a winding shaft **8** to which a ribbon roll obtained by winding the ink ribbon after the use is attached, and a printing unit **10**. The printing unit **10** is an example of the printing section described in the claims of this application. The vertical wall **202** of the housing **2** fixes one ends of the supply shaft **6**, the feeding shaft **7**, and the winding shaft **8**. That is, the vertical wall **202** holds the three shafts **6** to **8** in a cantilever state in a state in which the three shafts **6** to **8** are extended in the left-right direction.

(18) A fixing plate **9** is present in a position opposed to the end portions on the right side of the feeding shaft **7** and the winding shaft **8** separated from the vertical wall **202**. The fixing plate **9** is turnably connected to, via a hinge **901**, a supporting plate **205** erected upward from the bottom wall **201** of the housing **2**. The supporting plate **205** turnably supports the fixing plate **9** between an

illustrated fixing position that lies along a surface orthogonal to the left-right direction and a fixing release position illustrated in FIG. 7. The fixing plate **9** includes a receiving hole **902** that receives the distal end of the feeding shaft **7** in an illustrated state in which the fixing plate **9** turns to the fixing position and a receiving hole **903** that receives the distal end of the winding shaft **8**. The fixing plate **9** includes an insertion hole **904** through which a lock lever **101** for locking the printing unit **10** in an actuation position is inserted.

(19) The label paper roll **12** is obtained by winding long belt-like label paper **121** in a roll shape. The label paper **121** is obtained by pasting a plurality of labels **123** side by side on one surface of a long mount **122**. The label **123** includes an adhesive layer on a surface on the mount **122** side, can be pasted to and removed from the mount **122**, and can be pasted to another object after being peeled from the mount **122**. The label paper roll **12** is obtained by winding the label paper **121** on a tubular core material in a direction in which the surface of the mount **122** on which the label **123** is pasted is on the inner side. The label paper **121** is an example of the print medium described in the claims of this application. The print medium is not limited to the label paper **121** and may be, for example, belt-like heat sensitive paper.

(20) The ribbon roll is obtained by winding a long ribbon in a roll shape. The ink ribbon holds ink to be transferred to the label paper **121** by heat. The ribbon roll before use is obtained by winding the ink ribbon before transfer of the ink on a tubular shaft section. The diameter of the ribbon roll decreases if the ribbon roll is used. The ribbon roll after the use is obtained by winding the ink ribbon after the transfer of the ink with the tubular shaft section. The diameter of the ribbon roll gradually increases. The two ribbon rolls on the feeding side and the winding side may be integrally provided as a ribbon cassette.

(21) The supply shaft **6** includes, near both the ends in the longitudinal direction thereof, two hold plates **601** and **602** that are respectively in contact with both the end faces in the axial direction of the label paper roll **12**. The hold plate **601** on the left side close to the vertical wall **202** is movable to the left and the right in the longitudinal direction of the supply shaft **6**. The hold plate **601** determines an attachment position in the axial direction of the label paper roll **12** to match the center in the axial direction of the label paper roll **12** to a center surface of the label printer **100**. The center surface of the label printer **100** is an imaginary flat surface extending in the front-rear direction and the up-down direction that passes the center in the left-right direction of the printing unit **10**. In the following explanation, the imaginary surface is referred to as center surface of the label printer **100**. The hold plate **602** on the right side separated from the vertical wall **202** is also movable to the left and the right along the longitudinal direction of the supply shaft **6**. The hold plate **602** is fixed by a fixture **603** in any position that lies along the supply shaft **6**.

(22) If the label paper roll **12** is attached to the supply shaft **6**, the label paper roll **12** is attached to the supply shaft **6** in a state in which the hold plate **602** on the right side is detached from the supply shaft **6**. A direction in which the label paper roll **12** is attached is a direction in which the label paper **121** is drawn out in the direction of the printing unit **10** from the lower end side of the label paper roll **12** as illustrated in FIG. 7. After the label paper roll **12** is attached to the supply shaft **6**, the hold plate **602** is attached to the supply shaft **6**. The positions in the axial direction of the two hold plates **601** and **602** are adjusted such that the center in the axial direction of the label paper roll **12** is located on the center surface of the label printer **100**. The label paper roll **12** is positioned in the axial direction by the pair of hold plates **601** and **602**.

(23) If the ribbon rolls (or the ribbon cassette) are attached, the fixing plate **9** is opened to the fixing release position (FIG. 7) and the ribbon rolls are respectively attached to the feeding shaft **7** and the winding shaft **8**. The ink ribbon present between the feeding shaft **7** and the winding shaft **8** is disposed via a thermal head **11** (FIG. 8) of the printing unit **10**. After the ribbon rolls are attached, the fixing plate **9** is turned to a fixing position illustrated in FIG. 1, the distal end of the feeding shaft **7** is inserted through the receiving hole **902**, the distal end of the winding shaft **8** is inserted through the receiving hole **903**, the lock lever **101** is inserted through the insertion hole **904**, and

the lock lever **101** is turned to a lock position.

(24) The printing unit **10** is turnably connected to the right side surface of the vertical wall **202** of the housing **2** via a hinge mechanism. A turning shaft of the hinge mechanism extends in the front-rear direction. The printing unit **10** is extended in the left-right direction orthogonal to a conveyance direction of the label paper **121**. The printing unit **10** is turnable between an actuation position illustrated in FIG. **1** and a retracted position illustrated in FIG. **4**. The printing unit **10** includes a thermal head on the lower surface side thereof. The thermal head is disposed on the opposite side of the label paper **121** of the ink ribbon. A platen roller **13** (FIGS. **4** to **6**) is present in a position opposed to the thermal head across the label paper **121** and the ink ribbon in a state in which the printing unit **10** is disposed in the actuation position illustrated in FIG. **1**. In the state in which the printing unit **10** is disposed in the actuation position, the printing unit **10** presses the ink ribbon against the label paper **121** with the thermal head and thermally transfers the ink of the ink ribbon to the label paper **121**. The printing unit **10** prints a two-dimensional barcode or the like on the label **123** of the label paper **121**.

(25) The label printer **100** includes a conveyance guide unit **30** illustrated in FIG. **2** between the supply shaft **6** and the printing unit **10**. The conveyance guide unit **30** is present in a position closer to at least the printing unit **10** than the circumferential surface of the label paper roll **12** attached to the supply shaft **6**. The conveyance guide unit **30** is not illustrated in FIG. **1**. FIG. **2** is diagram of the conveyance guide unit **30** viewed from the rear of the label printer **100** (from the supply shaft **6** side).

(26) As illustrated in FIG. **2**, the conveyance guide unit **30** includes a pair of guide members **31** and **32** opposed to be separated from each other on the left and the right across a conveyance path of the label paper **121** drawn out from the label paper roll **12** attached to the supply shaft **6**. The guide members **31** and **32** are extended in the up-down direction. One guide member **31** is present on the left side (in FIG. **2**, the right side) close to the vertical wall **202**. The other guide member **32** is present in a position separated in the right direction (in FIG. **2**, the left direction) from the vertical wall **202**. The guide members **31** and **32** are attached to be movable to the left and the right with respect to the horizontal wall **204** (FIGS. **4** to **6**) of the housing **2**. In FIG. **2**, the horizontal wall **204** is not illustrated. The pair of guide members **31** and **32** is an example of the conveyance guide described in the claims of this application.

(27) The pair of guide members **31** and **32** is concurrently moved in the left-right direction by a rack and pinion mechanism **33**. The rack and pinion mechanism **33** includes a rack **331** extended in the right direction from a halfway portion in the up-down direction of the guide member **31** on the left side, a rack **332** extended in the left direction from a halfway portion in the up-down direction of the guide member **32** on the right side, and a pinion **333** that meshes with the two racks **331** and **332**. The racks **331** and **332** have lengths vertically overlapping across the pinion **333**. The pinion **333** includes a turning shaft extending in the front-rear direction and turnably attached to the housing **2**. The pair of guide members **31** and **32** is openable and closable in the left-right direction centering on the center surface of the label printer **100** by the rack and pinion mechanism **33**. Since the rack and pinion mechanism **33** is the well-known technique for those skilled in the art, detailed explanation of the rack and pinion mechanism **33** is omitted.

(28) The horizontal wall **204** of the housing **2** includes a slit **2041** (FIGS. **4** and **5**) through which a fixing screw **34** for fixing the guide member **32** on the right side to the horizontal wall **204** is slidably inserted. The slit **2041** pierces through the horizontal wall **204** in the front-rear direction and extends in the left-right direction, which is a moving direction of the guide members **31** and **32**. The guide member **32** includes an insertion hole through which the fixing screw **34** is inserted. The fixing screw **34** fixes, with joint fastening, a proximal end portion **351** of an arm **35**, which is formed by a sheet metal, to the horizontal wall **204** together with the guide member **32**.

(29) The arm **35** includes, in the proximal end portion **351** thereof, an insertion hole **352** through which the fixing screw **34** is inserted. A nut with which the fixing screw **34** is screwed is fixed on

the front surface of the insertion hole **352**. The distal end of the arm **35** is connected to a position sensor **36** explained below. In FIG. 2, the arm **35** is indicated by a solid line and indicated by a broken line. The solid line indicates the arm **35** in the case in which the pair of guide members **31** and **32** is fully opened. The broken line indicates the arm **35** in the case in which the pair of guide members **31** and **32** is fully closed. The arm **35** is an example of the coupling member described in the claims of this application.

(30) The pair of guide members **31** and **32** is openable and closable in the left-right direction by the rack and pinion mechanism **33** based on the center surface of the label printer **100**. The pair of guide members **31** and **32** adjusts an opening and closing width to match the length in the width direction orthogonal to the conveyance direction of the label paper **121** that passes between the pair of guide members **31** and **32**. Since the pair of guide members **31** and **32** is coupled by the rack and pinion mechanism **33**, one guide member moves in association with a movement of the other guide member. Therefore, the pair of guide members **31** and **32** can be fixed by fastening and fixing the guide member **32** on the right side to the horizontal wall **204** with the fixing screw **34** explained above. At the same time, the fixing screw **34** fixes the arm **35** to the horizontal wall **204**. In FIGS. 4 to 6, the arm **35** is hidden behind the horizontal wall **204** and unseen.

(31) A position sensor **36** for detecting the position in the width direction of the guide member **32** on the right side is present between the pair of guide members **31** and **32**. The position sensor **36** is extended in the left-right direction and fixed to a sheet metal **37** disposed in parallel to the horizontal wall **204** in the front of the horizontal wall **204**. The sheet metal **37** is fixed to the housing **2**. The position sensor **36** includes a slider pin **362** projecting to the rear via a slit **361** extended in the left-right direction. The slider pin **362** is movable to the left and the right along the slit **361**. A movable range of the slider pin **362** covers an entire movable range between the fully opened position and the fully closed position of the pair of guide members **31** and **32**.

(32) The position sensor **36** is a component of the conveyance guide unit **30** and is in close contact with the pair of guide members **31** and **32**. The conveyance guide unit **30** is in close contact with the printing unit **10** in a degree in which a movable range of the conveyance guide unit **30** and a movable range of the printing unit **10** do not interfere with each other. That is, the position sensor **36** is in close contact with the rear of the printing unit **10**.

(33) The arm **35** includes the proximal end portion **351** fixed to the guide member **32** on the right side and extends in the left direction. The arm **35** includes, near the distal end thereof, a slit **353** that receives the slider pin **362** of the position sensor **36**. The slit **353** pierces through the distal end of the arm **35** and extends in the up-down direction. If the guide member **32** on the right side moves in the left-right direction and the arm **35** moves in the left-right direction, the slider pin **362** of the position sensor **36** received in the slit **353** moves along the slit **361**.

(34) The position sensor **36** detects the position in the left-right direction of the slider pin **362**. As illustrated in FIG. 3, the position sensor **36** includes a long resistor **364** extended in the left-right direction. Voltages **V1** and **V2** are applied to both ends of the resistor **364**. The position sensor **36** outputs, as position information of the slider pin **362**, a voltage **V** that changes according to movement of the slider pin **362** conducted halfway in the longitudinal direction of the resistor **364**. The slider pin **362** is an example of the contactor described in the claims of this application.

(35) The guide members **31** and **32** respectively include pressing blocks **311** and **321** and guide plates **312** and **322**. For example, the pressing block **321** of the guide member **32** on the right side includes, at the lower end thereof, a pressing surface **3211** extending substantially horizontally. The pressing surface **3211** is opposed to the upper surface near the right end of the label paper **121** and presses the right end of the label paper **121** downward. The guide plate **322** of the guide member **32** on the right side includes, on the left side surface thereof, a guide surface **3221** parallel to the center surface of the label printer **100**. The guide surface **3221** is opposed to the right end of the label paper **121** and guides the right end of the label paper **121**. The pressing block **311** of the guide member **31** on the left side includes a pressing surface **3111** functioning in the same manner as the

pressing surface **3211**. The guide plate **312** on the left side includes, on the right side surface thereof, a guide surface **3121** that functions in the same manner as the guide surface **3221**.

(36) A procedure until the label paper **121** drawn out from the label paper roll **12** attached to the supply shaft **6** is projected from the front wall **203** of the label printer **100** through the printing unit **10** is explained with reference to FIGS. **4** to **7**. It is assumed that, before the label paper **121** is attached, the ink ribbon is already attached through the thermal head **11** of the printing unit **10**.

(37) First, as illustrated in FIG. **4**, the printing unit **10** is opened to the retracted position, the fixing screw **34** is loosened, and the pair of guide members **31** and **32** is opened to the left and the right. At this time, the pair of guide members **31** and **32** is opened slightly wider than the width of the label paper **121**. As illustrated in FIG. **5**, the distal end of the label paper **121** is fed forward to between the printing unit **10** and the platen roller **13**. The left and right ends of the label paper **121** are inserted below the pressing blocks **311** and **321** of the left and right pair of guide members **31** and **32**. Consequently, the left and right ends of the label paper **121** is pressed downward by the pressing surfaces **3111** and **3211** of the pressing blocks **311** and **321**.

(38) Thereafter, as illustrated in FIG. **6**, the distal end of the label paper **121** is drawn out to the front of the front wall **203** of the housing **2**. The pair of guide members **31** and **32** is moved in a direction for closing the pair of guide members **31** and **32** toward the left and right ends of the label paper **121**. The guide surfaces **3121** and **3221** of the left and right guide plates **312** and **322** are brought into contact with the left and right ends of the label paper **121**. At this time, the guide surfaces **3121** and **3221** of the left and right guide plates **312** and **322** may not be brought into contact with the left and right ends of the label paper **121** to provide small gaps between the label paper **121** and the guide members **31** and **32**. In this way, after the width between the pair of guide members **31** and **32** is adjusted, the fixing screw **34** is tightened to fix the pair of guide members **31** and **32** on the horizontal wall **204** of the housing **2**.

(39) Further, thereafter, as illustrated in FIG. **7**, the printing unit **10** is turned to the actuation position to hold the label paper **121** and the ink ribbon between the thermal head and the platen roller **13**. In this state, a conveying force can be applied to the label paper **121** from the platen roller **13**. The label paper **121** can be drawn out from the label paper roll **12**.

(40) Finally, the fixing plate **9** is turned from the fixing release position illustrated in FIG. **7** to the fixing position illustrated in FIG. **1**, the distal end of the feeding shaft **7** is inserted into the receiving hole **902**, the distal end of the winding shaft **8** is inserted into the receiving hole **903**, and the lock lever **101** of the printing unit **10** is inserted through the insertion hole **904**. The lock lever **101** is turned to lock the printing unit **10** in the actuation position.

(41) FIG. **8** is a block diagram illustrating a control system of the label printer **100** explained above.

(42) The label printer **100** includes a control section **50**, the operation and input section **206**, the display section **207**, the position sensor **36**, a lock sensor **52**, a storage section **54**, an arithmetic section **56**, a section setting **58**, and a communication section **59**.

(43) The control section **50** includes a CPU that controls an operation of the label printer **100**. The width of the label paper **121** used in the label printer **100** is input to the operation and input section **206**. The position sensor **36** detects the position in the width direction of the pair of guide members **31** and **32**. The lock sensor **52** senses that the lock lever **101** of the printing unit **10** is turned to the lock position. The lock sensor **52** is an example of the fixing sensor described in the claims of this application.

(44) The storage section **54** stores a voltage value output by the position sensor **36** if the pair of guide members **31** and **32** is disposed in the fully opened position and a voltage value output by the position sensor **36** if the pair of guide members **31** and **32** is disposed in the fully closed position. The fully closed position of the pair of guide members **31** and **32** is an example of the first position described in the claims of this application. The voltage value output by the position sensor **36** if the pair of guide members **31** and **32** is disposed in the fully opened position is an example of the first

output signal described in the claims of this application. The fully closed position of the pair of guide members **31** and **32** is an example of the second position described in the claims of this application. The voltage value output by the position sensor **36** if the pair of guide members **31** and **32** is disposed in the fully closed position is an example of the second output signal described in the claims of this application.

(45) The arithmetic section **56** creates, based on the two voltage values stored in the storage section **54**, a linear function indicating a characteristic of the position sensor **36**. The setting section **58** substitutes an output of the position sensor **36** in the linear function created by the arithmetic section **56** to determine width of the label paper **121** and sets a printing start position in the width direction for the label paper **121**. The setting section **58** is also an example of the correcting section described in the claims of this application. The communication section **59** transmits and receives various data to and from external equipment such as a host computer.

(46) A setting method for the printing start position by the label printer **100** is explained with reference to FIGS. **9** and **10**. Since the label printer **100** in this embodiment conveys the label paper **121** at center reference, it is assumed that a setting reference for the printing start position is the guide surface **3221** of the guide plate **322** of the guide member **32** that guides the right end in the width direction of the label paper **121**.

(47) Before the label paper roll **12** is attached, in ACT **1** in FIG. **9**, the control section **50** of the label printer **100** detects, in advance, voltage values output by the position sensor **36** if the pair of guide members **31** and **32** is disposed in the fully opened position where the pair of guide members **31** and **32** is opened to the maximum and the fully closed position where the pair of guide members **31** and **32** is brought close to each other until the distance between the pair of guide members **31** and **32** is minimized and stores the two voltage values in the storage section **54**.

(48) In ACT **2**, the control section **50** creates, based on the respective positions in the width direction at the time when the pair of guide members **31** and **32** is disposed in the fully opened position and the fully closed position and the two voltage values stored in the storage section **54** in ACT **1**, with the arithmetic section **56**, a linear function indicating a characteristic of the position sensor **36**. The linear function created in ACT **2** is stored in the storage section **54**. The positions in the width direction at the time when the pair of guide members **31** and **32** is fully opened and fully closed are positions in the width direction of the slider pin **362** of the position sensor **36** and are values including an individual difference and a detection error of the position sensor **36**.

(49) For example, as illustrated in FIG. **10**, if a position of the slider pin **362** of the position sensor **36** at the time when the pair of guide members **31** and **32** is disposed in the fully closed position is 15.5 mm, a voltage value detected by the position sensor **36** at that time is 3200 mV, a position of the slider pin **362** of the position sensor **36** at the time when the pair of guide members **31** and **32** is disposed in the fully opened position is 122 mm, and a voltage value detected by the position sensor **36** at that time is 500 mV, the linear function created by the arithmetic section **56** in ACT **2** can be represented by a straight line connecting the two points. That is, if the voltage value detected by the position sensor **36** is represented as V (mV) and the position of the slider pin **362** of the position sensor **36** is represented as W (mm), the linear function at this time is $W = -0.04V + 141.72$. The position in the width direction of the slider pin **362** represents the position in the width direction of the pair of guide members **31** and **32**.

(50) The label printer **100** can cause the storage section **54** to store, in advance, the widths of usable several kinds of label paper **121**. An operator attaches the label paper roll **12** to the supply shaft **6** as explained above and disposes, according to the procedure explained with reference to FIGS. **4** to **7**, the label paper **121** drawn out from the label paper roll **12** between the printing unit **10** and the platen roller **13**.

(51) After ACT **2**, if the label paper roll **12** is attached by the operator and the control section **50** senses, via the lock sensor **52**, that the lock lever **101** is turned to the lock position (YES in ACT **3**), in ACT **4**, the control section **50** detects the position in the width direction of the pair of guide

members **31** and **32** via the position sensor **36**. At this time, the control section **50** substitutes the voltage value detected via the position sensor **36** in the linear function created in ACT **2** and detects the position in the width direction of the pair of guide members **31** and **32**.

(52) A gap of approximately 1 mm often occurs between the pair of guide members **31** and **32**, and the label paper **121** which is detected in ACT **4**. Therefore, assuming that a gap of 0.5 mm is present on each of the left and the right between the label paper **121** and the pair of guide surfaces **3121** and **3221**, in ACT **5**, the control section **50** corrects the printing start position to be shifted 0.5 mm in the paper center direction. For example, if the distance between the guide surfaces **3121** and **3221** which is detected in ACT **4**, is 121 mm, the width of the label paper **121** attached to the label printer **100** is 120 mm. Gaps of 1 mm occur between the label paper **121** and the pair of guide surfaces **3121** and **3221**.

(53) That is, the control section **50** controls the setting section **58** based on a position obtained by adding the correction in ACT **5** to the position in the width direction of the pair of guide members **31** and **32** detected in ACT **4** and, in ACT **6**, sets a printing start position in the width direction for the label paper **121**. The printing start position is the position at the right end in the width direction of a printing region based on the guide surface **3221** of the guide plate **322** of the guide member **32** on the right side.

(54) After setting the printing start position in ACT **6**, in ACT **7**, the control section **50** displays setting information to the operator via the display section **207**. The information displayed via the display section **207** at this time is information concerning the position in the width direction of the pair of guide members **31** and **32**, information concerning the printing start position set in ACT **6**, and the like. The information concerning the printing start position includes a shift amount in the case in which the printing start position is shifted in the width direction. The information to be displayed can also be transmitted to external equipment via the communication section **59**.

(55) The operator can input a shift amount in the width direction of the printing start position via the operation and input section **206**. In this case, for example, if the operator inputs 10 mm as the shift amount in the width direction, the operator can shift the printing start position 10 mm in the left direction from a printing start reference, that is, the guide surface **3221** of the guide plate **322** of the guide member **32** on the right side.

(56) Effects of the embodiment explained above are explained below.

(57) According to this embodiment, based on an output of the position sensor **36** at the time when the pair of guide members **31** and **32** is disposed in the fully opened position and an output of the position sensor **36** at the time when the pair of guide members **31** and **32** is disposed in the fully closed position, a linear function indicating a relation between the outputs of the position sensor **36** and the position in the width direction of the pair of guide members **31** and **32** is created and the position in the width direction of the pair of guide members **31** and **32** is detected using the linear function. Therefore, according to this embodiment, it is possible to correct a lot or individual error or fluctuation of the position sensor **36** and more accurately detect the position in the width direction of the pair of guide members **31** and **32**. It is possible to securely set a printing start position in the width direction for the label paper **121**.

(58) In this embodiment, if the linear function serving as a control reference is created, sensor outputs at the time when the pair of guide members **31** and **32** is fully opened and at the time when the pair of guide members **31** and **32** is fully closed are sampled. Therefore, it is possible to minimize the influence of a characteristic error specific to the position sensor **36**. It is possible to more accurately detect the position in the width direction of the pair of guide members **31** and **32**. In the embodiment explained above, the data at the two points of the fully opened position and the fully closed position are sampled to create the linear function. However, for example, data at three points including an intermediate point illustrated in FIG. **11** may be sampled to create two linear functions. In this case, it is possible to further reduce the influence of the characteristic error specific to the position sensor **36**. Further, in this embodiment, the linear function is created as the

control reference. However, data at more points in the width direction may be sampled to create a control table.

(59) The label printer **100** in this embodiment includes, in close contact with the rear of the printing unit **10**, the conveyance guide unit **30** including the pair of guide members **31** and **32**. The conveyance guide unit **30** includes the position sensor **36** adjacent to the pair of guide members **31** and **32**. Therefore, according to this embodiment, it is possible to detect a conveyance position in the width direction of the label paper **121** immediately before the printing unit **10** in the conveyance direction of the label paper **121**. There is no concern that the label paper **121** deviates in the width direction and the printing start position deviates in a period until printing is performed after the conveyance position is detected. Therefore, according to this embodiment, even if a skew occurs in the label paper **121**, it is possible to prevent deviation from occurring in the printing start position in the width direction.

(60) In this embodiment, after the label paper roll **12** is set in the label printer **100** and the printing unit **10** is fixed in the actuation position, the data of the fully opened position and the fully closed position of the pair of guide members **31** and **32** are sampled to create the linear function serving as the control reference. Therefore, it does not occur that the pair of guide members **31** and **32** moves after the linear function creation to cause an error. Therefore, according to this embodiment, it is possible to accurately set the printing start position in the width direction.

(61) In this embodiment, if the operator holds the label paper **121** between the pair of guide members **31** and **32** and determines a conveyance position in the width direction, even if gaps of approximately 1 mm occur between the guide surfaces **3121** and **3221** of the pair of guide members **31** and **32** and the end portions of the label paper **121**, it is possible to correct the printing start position in the width direction. If the operator desires to intentionally change the printing start position, the operator can set a shift amount of the printing start position via the operation and input section **206**.

(62) In this embodiment, the arm **35** is fixed to the guide member **32** on the right side and the slider pin **362** of the position sensor **36** is coupled to the distal end of the arm **35**. Therefore, the position in the width direction of the pair of guide members **31** and **32** can be directly detected by the position sensor **36**. It is possible to markedly reduce a detection error.

(63) In the embodiment explained above, the data at the time when the pair of guide members **31** and **32** is disposed in the fully opened position and the fully closed position are sampled to create the linear function serving as the control reference. However, data to be sampled in order to create the linear function only has to be a plurality of data at the time when the pair of guide members **31** and **32** is disposed in different positions. The number of data to be sampled and the position in the width direction can be optionally set.

(64) In the embodiment explained above, the printing start position is corrected in ACT **5** in FIG. **9** assuming that the gaps of approximately 1 mm are present between the label paper **121** and the pair of guide members **31** and **32**. However, a difference between the width of the label paper **121** stored in advance in the storage section **54** and the width of the pair of guide members **31** and **32** detected in ACT **4** may be calculated and, if the difference does not exceed a preset threshold, the printing start position in the width direction for the label paper **121** may be set based on the width of the pair of guide members **31** and **32** detected in ACT **4**. If the difference does not exceed the preset threshold, the operator may set a printing start position based on the width of the label paper **121** input in advance by the operator. If the difference exceeds the preset threshold, the printing start position may be corrected based on the difference.

(65) While certain embodiment have been described, this embodiment has been presented by way of example only, and is not intended to limit the scope of invention. Indeed, the novel apparatus and methods described herein may be embodied in a variety of other forms; furthermore, various omissions, substitutions and changes in the form of the apparatus and methods described herein may be made without departing from the spirit of the inventions. The accompanying claims and

their equivalents are intended to cover such forms or modifications as would fall within the scope and spirit of the inventions.

Claims

1. A printer, comprising: a conveyance guide configured to guide an end portion of a print medium in a width direction orthogonal to a conveyance direction and determine a conveyance position in the width direction of the print medium, the conveyance guide movable in the width direction; a printing component configured to print on the print medium guided by the conveyance guide and conveyed in the conveyance direction; a position sensor configured to output a signal, which changes in proportion to a position in the width direction of the conveyance guide, and to detect the position in the width direction of the conveyance guide; wherein the position sensor comprises a resistor that applies a voltage to both ends of the resistor and is extended in the width direction and a contactor movable in the width direction in a state in which the resistor is conducted, the position sensor outputting a voltage corresponding to a position in the width direction of the contactor, an arithmetic component configured to create, based on a first output signal of the position sensor at a time when the conveyance guide is disposed in a first position in the width direction and a second output signal of the position sensor at a time when the conveyance guide is disposed in a second position different from the first position in the width direction, a linear function indicating a proportional relation between the position in the width direction of the conveyance guide and the output signals of the position sensor; a setting component configured to calculate, from the output signals of the position sensor, the position in the width direction of the conveyance guide using the linear function created by the arithmetic component and set, based on the calculated position, a printing start position in the width direction by the printing component for the print medium; and a coupling member connected to the contactor and provided integrally with the conveyance guide.
2. The printer according to claim 1, further comprising: a housing; and a fixing screw for fixing the conveyance guide and the coupling member to the housing with joint fastening.
3. The printer according to claim 2, further comprising a sheet metal fixed to the housing, wherein the position sensor is fixed to the sheet metal.
4. The printer according to claim 1, further comprising: an input component to which length in the width direction of the print medium is input; and a correcting component configured to calculate, based on the position in the width direction of the conveyance guide calculated by the setting component and the length in the width direction input via the input component, a length in the width direction of a gap between the end portion of the print medium and the conveyance guide and correct, by the gap, the printing start position set by the setting component.
5. The printer according to claim 4, wherein the correcting component compares the calculated length in the width direction of the gap with a preset threshold, if the length in the width direction of the gap exceeds the threshold, corrects the printing start position, and, if the length in the width direction of the gap does not exceed the threshold, does not correct the printing start position.
6. The printer according to claim 4, wherein the conveyance guide includes a pair of guide members configured to guide both ends, of the print medium, in the width direction of the print medium, the pair of guide members movable in the width direction, and the correcting component corrects the printing start position by a half of the calculated length in the width direction of the gap.
7. The printer according to claim 1, wherein the conveyance guide includes a pair of guide members configured to guide both ends, of the print medium, in the width direction of the print medium, the pair of guide members being openable and closable in the width direction, and the arithmetic component creates the linear function using, as the first output signal, an output signal of the position sensor at a time when the pair of conveyance guides is disposed in a fully opened state and using, as the second output signal, an output signal of the position sensor at a time when the

pair of conveyance guides is disposed in a fully closed state.

8. The printer according to claim 1, further comprising a fixing sensor configured to sense that the printing component is fixed in an actuation position, wherein the arithmetic component acquires, based on sensing, via the fixing sensor, that the printing component is fixed in the actuation position, the first output signal and the second output signal and creates the linear function.

9. A method, comprising: guiding an end portion of a print medium with a conveyance guide in a width direction orthogonal to a conveyance direction and determining a conveyance position in the width direction of the print medium, the conveyance guide movable in the width direction; printing on the print medium guided by the conveyance guide and conveyed in the conveyance direction; outputting a signal from a position sensor, which changes in proportion to a position in the width direction of the conveyance guide, and detecting the position in the width direction of the conveyance guide; creating, based on a first output signal of the position sensor at a time when the conveyance guide is disposed in a first position in the width direction and a second output signal of the position sensor at a time when the conveyance guide is disposed in a second position different from the first position in the width direction, a linear function indicating a proportional relation between the position in the width direction of the conveyance guide and the output signals of the position sensor; and calculating, from the output signals of the position sensor, the position in the width direction of the conveyance guide using the linear function created by the arithmetic component and set, based on the calculated position, a printing start position in the width direction by the printing component for the print medium, wherein the conveyance guide comprises a pair of guide members configured to guide both ends, of the print medium, in the width direction of the print medium, the pair of guide members being openable and closable in the width direction, and wherein the arithmetic component creates the linear function using, as the first output signal, an output signal of the position sensor at a time when the pair of conveyance guides is disposed in a fully opened state and using, as the second output signal, an output signal of the position sensor at a time when the pair of conveyance guides is disposed in a fully closed state.

10. The method according to claim 9, wherein the position sensor comprises a resistor and a contactor movable in the width direction in a state in which the resistor is conducted, the method further comprising: applying a voltage to both ends of the resistor corresponding to a position in the width direction of the contactor.

11. The method according to claim 9, further comprising: sensing that the printing component is fixed in an actuation position; and acquiring, based on sensing, that the printing component is fixed in the actuation position, the first output signal and the second output signal and creating the linear function.

12. The method according to claim 9, further comprising: inputting a length in the width direction of the print medium; and calculating, based on the position in the width direction of the conveyance guide calculated and the length in the width direction input, a length in the width direction of a gap between the end portion of the print medium and the conveyance guide and correcting, by the gap, the printing start position set.

13. The method according to claim 12, further comprising: comparing the calculated length in the width direction of the gap with a preset threshold; and if the length in the width direction of the gap exceeds the threshold, correcting the printing start position; and if the length in the width direction of the gap does not exceed the threshold, not correcting the printing start position.

14. The method according to claim 12, further comprising: guiding both ends in the width direction of the print medium with a pair of guide members of the conveyance guide, the pair of guide members movable in the width direction; and correcting the printing start position by a half of the calculated length in the width direction of the gap.

15. A label printer, comprising: a print head; a conveyance guide configured to guide an end portion of a print medium in a width direction orthogonal to a conveyance direction and determine a conveyance position in the width direction of the print medium, the conveyance guide movable in

the width direction; a printing component configured to print on the print medium guided by the conveyance guide and conveyed in the conveyance direction; a position sensor configured to output a signal, which changes in proportion to a position in the width direction of the conveyance guide, and to detect the position in the width direction of the conveyance guide; wherein the position sensor includes a resistor that applies a voltage to both ends of the resistor and is extended in the width direction and a contactor movable in the width direction in a state in which the resistor is conducted, the position sensor outputting a voltage corresponding to a position in the width direction of the contactor, an arithmetic component configured to create, based on a first output signal of the position sensor at a time when the conveyance guide is disposed in a first position in the width direction and a second output signal of the position sensor at a time when the conveyance guide is disposed in a second position different from the first position in the width direction, a linear function indicating a proportional relation between the position in the width direction of the conveyance guide and the output signals of the position sensor; a setting component configured to calculate, from the output signals of the position sensor, the position in the width direction of the conveyance guide using the linear function created by the arithmetic component and set, based on the calculated position, a printing start position in the width direction by the printing component for the print medium; and a coupling member connected to the contactor and provided integrally with the conveyance guide.
