

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250284370

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

TANAKA; Sakae

DISPLAY DEVICE WITH TOUCH SENSOR

Abstract

A display device with a touch and fingerprint sensor includes a display part including a plurality of data signal lines, at least one first sensor electrode, a terminal part including a first terminal, and a second terminal, and a switching circuit disposed between the display part and the terminal part and including one input terminal and a plurality of output terminals, and dividing an input signal input to the one input terminal to the plurality of output terminals. The one input terminal is connected to the first terminal, the plurality of data signal lines is connected to the plurality of output terminals, and the at least one first sensor electrode is connected to the second terminal.

Inventors: TANAKA; Sakae (Saitama, JP)

Applicant: MIKUNI ELECTRON CORPORATION (Saitama, JP)

Family ID: 81382633

Appl. No.: 19/214357

Filed: May 21, 2025

Foreign Application Priority Data

JP	2020-182821	Oct. 30, 2020
----	-------------	---------------

Related U.S. Application Data

parent US continuation 18307845 20230427 parent-grant-document US 12333118 child US 19214357

parent WO continuation PCT/JP2021/040143 20211029 PENDING child US 18307845

Publication Classification

Int. Cl.: G06F3/044 (20060101); G02F1/1362 (20060101); G02F1/1365 (20060101)

U.S. Cl.:

CPC **G06F3/0446** (20190501); **G02F1/136218** (20210101); **G02F1/136286** (20130101);
G02F1/1365 (20130101);

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This is a continuation of U.S. patent application Ser. No. 18/307,845 filed on Apr. 27, 2023, which is a Continuation of International Patent Application No. PCT/JP2021/040143 filed on Oct. 29, 2021, which claims the benefit of priority to Japanese Patent Application No. 2020-182821 filed on Oct. 30, 2020, the entire contents of which are incorporated herein by reference.

FIELD

[0002] An embodiment of the present invention relates to a display device with a sensor capable of detecting biological information such as fingerprints, palm prints in addition to its function as a touch sensor.

BACKGROUND

[0003] To prevent unauthorized use and protect personal information, the development of electronic devices that identify users through biometric identification is underway. For example, a display device having a fingerprint authentication sensor mounted on the back of a display panel in which pixels are formed with an organic light emitting diode is disclosed (refer to Japanese Laid-Open Patent Publication No. 2018-085114). A touch sensor is also disposed on the display panel to disclose a display device capable of recognizing fingerprints and touch pressures (refer to Japanese Laid-Open Patent Publication No. 2018-005910).

[0004] The market needs for portable electronics, where display screens occupy the entire front of the device, are to allow fingerprint authentication anywhere on the display screen to enhance functionality. In response to this need, there is a problem that a display device, such as disclosed in Japanese Laid-Open Patent Publication No. 2018-085114, cannot detect fingerprints throughout the screen because a sensor for fingerprint authentication is mounted as a small discrete component. If you try to make fingerprint authentication possible on all screens, the casing becomes larger.

[0005] On the other hand, the display device disclosed in Japanese Laid-Open Patent Publication No. 2018-005910 has the problem of significantly increasing the number of connecting terminals for the input/output of signals due to the complete separation of the circuitry for performing image display and the circuitry for driving the fingerprint sensor. The dimensions of the display panels are determined by the electronics to be mounted, and the location where the connecting terminal can be located is limited. Accordingly, when adding a terminal that outputs the signals of the fingerprint sensor in addition to the connecting terminal for inputting the video signals, it is necessary to narrow the pitch of the connecting terminal. However, when the pitch of the terminal electrodes is narrowed, it becomes difficult to connect the flexible wiring board using a conventional anisotropic conductive film (ACF), resulting in a decrease in yield.

SUMMARY

[0006] A display device with a touch and fingerprint sensor in an embodiment according to the present invention includes a display part including a plurality of data signal lines, at least one first sensor electrode, a terminal part including a first terminal and a second terminal, and a switching circuit disposed between the display part and the terminal part, including one input terminal and a plurality of output terminals, and dividing an input signal input to the one input terminal to the plurality of output terminals. The one input terminal is connected to the first terminal, the plurality of data signal lines is connected to the plurality of output terminals, and the at least one first sensor

electrode is connected to the second terminal.

[0007] A display device with a touch and fingerprint sensor in an embodiment according to the present invention includes a first sensor electrode extending in a first direction and a second sensor electrode extending in a second direction intersecting the first direction, a scanning signal line extending in the second direction, a pixel overlapping the second sensor electrode, and a transistor disposed in the pixel. A gate electrode of the transistor is connected to the scanning signal line, and the scanning signal line is connected to the second sensor electrode.

Description

BRIEF DESCRIPTION OF DRAWINGS

[0008] FIG. 1 is a developed view of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0009] FIG. 2 is a configuration of a display part, a touch and fingerprint sensor part, a switching circuit, and a drive circuit of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0010] FIG. 3A is a timing chart explaining the operation of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0011] FIG. 3B is a timing chart explaining the operation of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0012] FIG. 4 is an example of an equivalent circuit of a pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0013] FIG. 5 is a configuration of switching circuits, a terminal part, and a second drive circuit of a display device with touch and fingerprint sensor according to an embodiment of the present invention.

[0014] FIG. 6 is a configuration of switching circuits, a terminal part, and a second drive circuit of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0015] FIG. 7 is a configuration of switching circuits, a terminal part, and a second drive circuit of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0016] FIG. 8 is a configuration of switching circuits, a terminal part, and a second drive circuit of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0017] FIG. 9 is an arrangement of pixels and first and second sensor electrodes of a display device with a touch and fingerprint sensors according to an embodiment of the present invention.

[0018] FIG. 10 is an arrangement of pixels and first and second sensor electrodes of a display device with touch and fingerprint sensors, and shows an example where the first sensor electrode is disposed at a ratio of one for two pixel rows and the second sensor electrode is disposed at a ratio of one for two pixel rows.

[0019] FIG. 11A is a top view of a first sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0020] FIG. 11B is a cross-sectional view corresponding to the line A1-A2 shown in a top view of a first sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0021] FIG. 12A is a top view of a first sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0022] FIG. 12B is a cross-sectional view corresponding to the line B1-B2 shown in a top view of a first sensor electrode of a display device with a touch and fingerprint sensor according to an

embodiment of the present invention.

[0023] FIG. **13A** is a top view of a second sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0024] FIG. **13B** is a cross-sectional view corresponding to the line C1-C2 shown in a top view of a second sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0025] FIG. **14A** is a top view of a second sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0026] FIG. **14B** is a cross-sectional view corresponding to the line C3-C4 shown in a top view of a second sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0027] FIG. **14C** is a cross-sectional view corresponding to the line C5-C6 shown in a top view of a second sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0028] FIG. **15** is an example of a planar layout of a drive transistor, a select transistor, a capacitive element, and an EL element that constitute a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0029] FIG. **16A** is a cross sectional view corresponding to the line D1-D2 shown in FIG. **15**, and shows the configuration of the sub-pixel of the display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0030] FIG. **16B** is a cross sectional view corresponding to the line D3-D4 shown in FIG. **15**, and shows the configuration of the sub-pixel of the display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0031] FIG. **17** is an example of a planar layout of a drive transistor, a select transistor, a capacitive element, and an EL element that constitute a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0032] FIG. **18** is an example of a planar layout of a drive transistor, a select transistor, a capacitive element, and an EL element that constitute a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0033] FIG. **19A** is a cross sectional view corresponding to the line D5-D6 shown in FIG. **18**, and shows the configuration of the sub-pixel of the display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0034] FIG. **19B** is a cross sectional view corresponding to the line D7-D8 shown in FIG. **18**, and shows the configuration of the sub-pixel of the display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0035] FIG. **20** is an example of a planar layout of a drive transistor, a select transistor, a capacitive element, and an EL element that constitute a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0036] FIG. **21A** is a cross sectional view corresponding to the line D9-D10 shown in FIG. **20**, and shows the configuration of the sub-pixel of the display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0037] FIG. **21B** is a cross sectional view corresponding to the line D11-D12 shown in FIG. **20**, and shows the configuration of the sub-pixel of the display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0038] FIG. **22A** is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, in which a light shielding layer extends below a terminal part.

[0039] FIG. **22B** is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, in which a first insulating layer extends below a terminal part.

[0040] FIG. **23A** is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, in which a light shielding layer extends below a terminal part and a second insulating layer extends above the drawer wiring.

[0041] FIG. **23B** is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, in which a first insulating layer extends below a drawer wiring and a second insulating layer extends above the drawer wiring.

[0042] FIG. **24A** is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, in which a light shielding layer, a first insulating layer, and a second insulating layer extend below a drawer wiring and a terminal part.

[0043] FIG. **24B** is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, in which a first insulating layer and a second insulating layer extend below a terminal part.

[0044] FIG. **25A** is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, in which a light shielding layer is disposed below a terminal part and a drawer wiring is connected to the first sensor electrode via a plurality of contact holes.

[0045] FIG. **25B** is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, in which the drawer wiring is connected to the first sensor electrode via a plurality of contact holes.

[0046] FIG. **26** is a configuration of the display part, a touch and fingerprint sensor part, switching circuits, and a flexible circuit board of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0047] FIG. **27** is a wiring structure of a flexible circuit board of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0048] FIG. **28** is a connection structure of a terminal part and a flexible circuit board of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0049] FIG. **29** is a configuration for connecting a terminal part and a flexible circuit board of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0050] FIG. **30** is a configuration of a display part, a touch and fingerprint sensor, switching circuits, and a flexible circuit board of a touch and fingerprint sensor according to an embodiment of the present invention.

[0051] FIG. **31** is a wiring structure of a flexible circuit board of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0052] FIG. **32** is a configuration of a display part, a touch and fingerprint sensor, switching circuits, and a drive circuit of a touch and fingerprint sensor according to an embodiment of the present invention.

[0053] FIG. **33** is an example of an output switching circuit of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0054] FIG. **34** is an example of an output switching circuit of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0055] FIG. **35** is a configuration of a display part, a touch and fingerprint sensor, switching circuits, and a drive circuit of a touch and fingerprint sensor according to an embodiment of the present invention.

[0056] FIG. **36A** is a top view of a second sensor electrode of a display device with a touch and

fingerprint sensor according to an embodiment of the present invention.

[0057] FIG. **36B** is a cross-sectional view corresponding to the line C7-C8 shown in a top view of the second sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of present invention.

[0058] FIG. **36C** is a cross-sectional view corresponding to the line C7-C8 shown in a top view of the second sensor electrode of a display device with a touch and fingerprint sensor according to an embodiment of present invention.

[0059] FIG. **37** is a timing chart explaining the operation of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0060] FIG. **38** is a configuration of a display part, a touch and fingerprint sensor, switching circuit, and drive circuit of a touch and fingerprint sensor according to an embodiment of the present invention.

[0061] FIG. **39** is a configuration of a display part, a touch and fingerprint sensor, switching circuit, and drive circuit of a touch and fingerprint sensor according to an embodiment of the present invention.

[0062] FIG. **40** is a connecting structure of the terminal part and drive circuit of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0063] FIG. **41** is an example of an equivalent circuit of pixels disposed in a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0064] FIG. **42** is a timing chart explaining a method for driving a pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0065] FIG. **43** is an example of an equivalent circuit of pixels disposed in a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0066] FIG. **44** is a timing chart explaining a method for driving a pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0067] FIG. **45** is a connection structure of the terminal part and a flexible circuit board of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0068] FIG. **46** is a configuration of a display part, a touch and fingerprint sensor, switching circuit, and drive circuit of a touch and fingerprint sensor according to an embodiment of the present invention.

[0069] FIG. **47** is an arrangement of a data signal line and a common wiring disposed on a display part of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0070] FIG. **48** is an example of a planar layout of a drive transistor, a select transistor, a capacitive element, and an EL element that constitutes a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0071] FIG. **49** is a cross-sectional view of a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0072] FIG. **50** is a planar layout of an organic EL elements disposed on a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention and a cross-sectional structure of the lines E1-E2 and E3-E4 shown in the figure.

[0073] FIG. **51** is an example of an equivalent circuit of pixels disposed in a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0074] FIG. **52** is an example of a planar layout of a drive transistor, a select transistor, a capacitive element, and an EL element that constitutes a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0075] FIG. **53** is a cross-sectional view of a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0076] FIG. **54** is an example of a planar layout of a drive transistor, a select transistor, a capacitive element, and an EL element that constitutes a sub-pixel of a display device with a touch and

fingerprint sensor according to an embodiment of the present invention.

[0077] FIG. 55 is a cross-sectional view of a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0078] FIG. 56 is a cross-sectional view of a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, and shows a structure with a wire-grid polarizer and a light scattering layer.

[0079] FIG. 57 is a cross-sectional view of a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, and shows a structure with a wire-grid polarizer and a light scattering layer.

[0080] FIG. 58 is a cross-sectional configuration of a wire-grid polarizer disposed on a display part of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0081] FIG. 59 is a cross-sectional configuration of a wire-grid polarizer disposed on a display part of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0082] FIG. 60 is a diagram of a relationship between a wire-grid polarizer and a polarization axis of a polarization axis rotator in a display part of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0083] FIG. 61 is an arrangement of a wire-grid polarizer on a display part of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0084] FIG. 62 is an arrangement of a wire-grid polarizer on a display part of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0085] FIG. 63A is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment present invention, and shows a connection structure between a second sensor electrode and a drawer wiring formed in the same layer as a data signal line.

[0086] FIG. 63B is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment present invention, and shows a connection structure between a second sensor electrode, and a drawer wiring formed in the same layer as a scanning signal line.

[0087] FIG. 64A is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment present invention, and shows a connection structure between a first sensor electrode, and a drawer wiring formed in the same layer as a scanning signal line.

[0088] FIG. 64B is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment present invention, and shows a connection structure between a second electrode of an organic EL element and a drawer wiring.

[0089] FIG. 65A is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment present invention, and shows a connection structure between a data signal line and a drawer wiring.

[0090] FIG. 65B is an example of a connection structure between a first sensor electrode and a drawer wiring of a display device with a touch and fingerprint sensor according to an embodiment present invention, and shows a connection structure between a second sensor electrode and a drawer wiring.

[0091] FIG. 66 is a cross-sectional view of a sub-pixel of a display device with a touch and fingerprint sensor according to an embodiment of the present invention, and shows a structure with a wire-grid polarizer and a light scattering layer.

[0092] FIG. 67 is an arrangement of a wire-grid polarizer on a display part of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

[0093] FIG. **68** is a cross-sectional structure and operating principles of a wire-grid polarizer disposed on the display part of a display device with a touch and fingerprint sensor according to an embodiment of the present invention.

DESCRIPTION OF EMBODIMENTS

[0094] Hereinafter, embodiments of the present invention are described with reference to the drawings. However, the present invention can be implemented in many different aspects, and should not be construed as being limited to the description of the following embodiment. For the sake of clarifying the explanation, the drawings may be expressed schematically with respect to the width, thickness, shape, and the like of each part compared to the actual aspect, but this is only an example and does not limit the interpretation of the present invention. For this specification and each drawing, elements similar to those described previously with respect to previous drawings may be given the same reference sign (or a number followed by A, B, etc.) and a detailed description may be omitted as appropriate. The terms “first” and “second” appended to each element are a convenience sign used to distinguish them and have no further meaning except as otherwise explained.

[0095] As used herein, where a member or region is “on” (or “below”) another member or region, this includes cases where it is not only directly on (or just under) the other member or region but also above (or below) the other member or region, unless otherwise specified. That is, it includes the case where another component is included in between above (or below) other members or regions.

First Embodiment

[0096] This embodiment shows an example of a display device in which a display part and a touch and a fingerprint sensor are disposed over each other.

1-1. Configuration of Display Device with Touch and Fingerprint Sensor

[0097] FIG. **1** shows an expanded view of a display device with a touch and fingerprint sensor **100** according to an embodiment of the present invention. The display device with a touch and fingerprint sensor **100** includes a display part **102** with a plurality of pixels **104** arranged therein and a touch and fingerprint sensor **110** including at least one first sensor electrode **112** and at least one second sensor electrode **114**. A shield electrode **116** is disposed between the display part **102** and the touch and fingerprint sensor **110**.

[0098] The at least one first sensor electrode **112** is arranged to extend in a Y direction and the at least one second sensor electrode **114** is arranged to extend in an X direction. The at least one first sensor electrode **112** includes a plurality of first sensor electrodes (hereinafter similarly labeled “**112**”) and the plurality of first sensor electrodes **112** are arranged in the X direction. The at least one second sensor electrode **114** includes a plurality of second sensor electrodes (hereinafter similarly labeled “**114**”) and the plurality of second sensor electrodes **114** are arranged in the Y direction. The plurality of first sensor electrodes **112** and the plurality of second sensor electrodes **114** are arranged to intersect an insulating layer (not shown in the figure).

[0099] An outer region of the display part **102** is disposed with a first drive circuit **118**, a switching circuit **120** (also referred to as a “multiplexer circuit” or a “demultiplexer”), and a terminal part **122**. The shield electrode **116** is disposed to electrically isolate the display part **102** from the touch and fingerprint sensor **110**. A constant potential (for example, ground potential) is applied to the shield electrode **116**.

[0100] Each of the plurality of pixels **104** includes a light emitting element. For example, an electroluminescent element (hereinafter referred to as an “EL element”) is used as a light emitting element. The EL elements disposed in each of the plurality of pixels **104** are bottom emission type elements that emit light toward the side of the shield electrode **116**. The first sensor electrode **112**, the second sensor electrode **114**, and the shield electrode **116** are translucent. The first sensor electrode **112**, the second sensor electrode **114**, and the shield electrode **116** are formed of a transparent conductive film. Alternatively, the first sensor electrode **112**, the second sensor

electrode **114**, and the shield electrode **116** may be disposed with openings in accordance with the placement of the plurality of pixels **104**. With such an arrangement, the light emission of the EL elements is emitted through the shield electrode **116** and the touch and fingerprint sensor **110**.

[0101] The display device with a touch and fingerprint sensor **100** has a configuration for viewing the images displayed on the display part **102** from the side on which the touch and fingerprint sensor **110** is disposed. Since the touch and fingerprint sensor **110** is disposed to overlap the display part **102**, the display device with the touch and fingerprint sensor **100** is capable of detecting a touch and fingerprint at any position on the display screen.

[0102] A sealing layer **124** may be disposed on the display part **102**. The sealing layer **124** is disposed to protect the display part **102**, the first drive circuit **118**, and the switching circuit **120**. A configuration of the sealing layer **124** is optional. For example, the sealing layer **124** is formed of an inorganic insulating film such as a silicon oxide film or a silicon nitride film. The sealing layer **124** may also be formed of a resinous material such as a polyimide resin, an acrylic resin, or an epoxy resin.

[0103] FIG. 2 shows the display part **102** of the display device with a touch and fingerprint sensor **100** according to the present embodiment, and shows the touch and fingerprint sensor **110**, the first drive circuit **118**, the switching circuit **120**, the terminal part **122**, and a second drive circuit **128**. The display part **102**, the touch and fingerprint sensor **110**, the first drive circuit **118**, the switching circuit **120**, and the terminal part **122** are disposed on a transparent resin substrate **200**. The second drive circuit **128** is disposed on a flexible circuit board **126**. The second drive circuit **128** is implemented in the flexible circuit board **126** by a COF (Chip on Film) method.

[0104] The display part **102** includes the plurality of pixels **104**. The plurality of pixels **104** may be arranged in an array such as, for example, a stripe array, a delta array, a “Bayer” array, a “PenTile” array, a “Diamond PenTile” array, or the like. The display part **102** is disposed with a data signal line **108** and a scanning signal line (not shown in the figure). For the plurality of pixels **104** arranged in a first (column) direction and a second (row) direction, the data signal line **108** extends in the first (column) direction and the scanning signal line extends in the second (row) direction intersecting the first direction.

[0105] The first drive circuit **118** is disposed in an outer region of the display part **102** (hereinafter referred to as the “peripheral area”). The first drive circuit **118** is connected to a scanning signal line not shown in the figure. The first drive circuit **118** is disposed along one side of the display part **102**. The plurality of data signal lines **108**, not shown, are arranged in the first direction (column direction) and connected to the switching circuit **120**.

[0106] The terminal part **122** with an array of a plurality of connecting terminals is disposed at one end of the transparent resin substrate **200**. The switching circuit **120** is disposed in an area between the display part **102** and the terminal part **122**. The switching circuit **120** has the ability to distribute one input to a plurality of output terminals. The switching circuit **120** connects one connecting terminal disposed in the terminal part **122** to a plurality of data signal line **108**.

[0107] The touch and fingerprint sensor **110** includes the plurality of first sensor electrodes **112** extending in the first direction (column direction) and a plurality of second sensor electrodes **114** extending in the second direction (row direction). Each of the plurality of first sensor electrodes **112** is connected to a connecting terminal disposed on the terminal part **122**. The plurality of second sensor electrodes **114** are connected to the first drive circuit **118**. The plurality of first sensor electrodes **112** and the plurality of second sensor electrodes **114** are arranged to intersect an insulating layer (not shown) and serve as fingerprint sensors and touch sensors.

[0108] The flexible circuit board **126** includes wirings that connect the first drive circuit **118**, the switching circuit **120**, and the first sensor electrode **112** to the second drive circuit **128**. The flexible circuit board **126** is connected to the connecting terminal of the terminal part **122** via anisotropic conductive materials. A scanning signal line drive circuit block **130** of the second drive circuit **128** is connected to the first drive circuit **118**, a data signal line drive circuit block **132** is connected to

the switching circuit **120**, and a touch and fingerprint sensor detection circuit block **134** is connected to the first sensor electrode **112**.

[0109] In the second drive circuit **128**, the scanning signal line drive circuit block **130** has the function of outputting a signal for driving the first drive circuit **118** outputting the scanning signal of the display unit **102** and the scanning signal of the touch and fingerprint sensor unit **110**, the data signal line drive circuit block **132** has the function of outputting a video signal, and the touch and fingerprint sensor detection circuit block **134** has the function of amplifying the sensing signal output from the first sensor electrode **112** to generate a digital signal as a sensor output.

[0110] FIG. 2 shows an example in which the second drive circuit **128** is disposed with a composite integrated circuit (composite IC) that integrates a plurality of circuit blocks into one semiconductor chip. Such a composite integrated circuit can reduce the number of processes compared to mounting individual IC chips, thereby reducing manufacturing costs. Note that the second drive circuit **128** is not limited to this example, and may employ one in which each of the circuit blocks is implemented in a separate integrated circuit.

[0111] FIG. 3A and FIG. 3B shows timing charts of the display device with the touch and fingerprint sensor **100** shown in FIG. 2. The first drive circuit **118** of the display device with the touch and fingerprint sensor **100** serves as the scanning signal line drive circuit for the display part **102** and the scan signal output circuit for the touch and fingerprint sensor unit **110**. Thus, the display device with the touch and fingerprint sensor **100** is driven to alternate between the display period and the sensing period.

[0112] FIG. 3A shows an example of a sensing period occurring for each display period of one frame. FIG. 3B shows an example of a sensing period occurring at one time during a two-frame display period. The length of the sensing period is optional and can be set shorter than one frame period. Since the frame frequency is 60 Hz or higher, the touch or fingerprint sensing can be performed while displaying the image, with no visual impact on the display part **102**, even if there is a sensing period between frames.

1-2. Equivalent Circuit of Pixel

[0113] FIG. 4 shows an example of an equivalent circuit of a pixel **104**. The pixel **104** includes a first sub-pixel **105r**, a second sub-pixel **105g**, and a third sub-pixel **105b**. The first sub-pixel **105r** includes a drive transistor **136**, a select transistor **138**, a capacitive element **140**, and an EL element **142**. The second sub-pixel **105g** and the third sub-pixel **105b** have the same configuration. In FIG. 4, the symbol representing the drive transistor **136** and the select transistor **138** is a dual gate structure that sandwiches the semiconductor layer with two gate electrodes. The drive transistor **136** has a first gate electrode **150** which is arranged on the lower side and a second gate electrode **151** which is arranged on the upper side, and the select transistor **138** has a first gate electrode **152** which is arranged on the lower side and a second gate electrode **153** which is arranged on the upper side. The drive transistor **136** and the select transistor **138** are n-channel transistors.

[0114] The second gate electrode **153** of the select transistor **138** is connected to a scanning signal line **106a**, the source to the data signal line **108**, and the drain to the capacitive element **140** and the second gate electrode **151** of the drive transistor **136**. The first gate electrode **150** of the drive transistor **136** is connected to a common wiring **144b**, the source to a common electrode **144a**, and the drain to the cathode of the EL element **142**. One terminal (first terminal) of the capacitive element **140** is connected to the drain of the selectable transistor **138** and the other terminal is connected to the common wiring **144b**. The anode of EL element **142** is connected to a power line **154**.

[0115] In FIG. 4, the common electrode **144a** and the common wiring **144b** are shown separately in the equivalent circuit, but both are functionally identical in that they are at the same potential and are secured to a constant potential (for example, a ground potential). The power line **154** is applied with a power supply potential VDD that is higher than the potential of the common electrode **144a**, and common wiring **144b**. When the drive transistor **136** is on, the EL element **142** is in a state in

which current flows from the power line **154** to the common electrode **144a**. The current flowing at this time is also the drain current of the drive transistor **136**, and the potential of the second gate electrode **151** can control the current amount (which is also the emission intensity of the EL element).

[0116] The equivalent circuit of the pixel shown in FIG. **4** is an example, and the display device with the touch and fingerprint sensor **100** according to the present embodiment can also apply pixel circuitry having other circuit configurations. For example, the pixel circuit incorporating a circuit that compensates for the threshold voltage of the drive transistor may be applied.

1-3. Switching Circuit

[0117] FIG. **5** shows the configuration of the switching circuit **120** (**120_1** to **120_h**), the terminal part **122**, and the second drive circuit **128** of the display device with the touch and fingerprint sensor **100** according to the present embodiment. The switching circuit **120** (**120_1** to **120_h**) and the terminal part **122** are disposed in the transparent resin substrate **200**. The second drive circuit **128** is implemented in the flexible circuit board **126**.

[0118] The terminal part **122** includes a first connecting terminal **146a** and a second connecting terminal **146b**. The first connecting terminal **146a** is a terminal connected to the switching circuit **120** (**120_1** to **120_h**), and the second connecting terminal **146b** is a terminal connected to the first sensor electrode **112** (**112_1** to **112_k**). The flexible circuit board **126** includes a third connecting terminal **148a** and a fourth connecting terminal **148b**. The first connecting terminal **146a** is connected to the third connecting terminal **148a** and the second connecting terminal **146b** is connected to the fourth connecting terminal **148b**. The connecting terminals disposed on the transparent resin substrate **200** and the connecting terminals disposed on the flexible circuit board **126** are connected by an anisotropic conductive adhesive.

[0119] The switching circuit **120** (**120_1** to **120_h**) includes one input terminal and three output terminals. The switching circuit **120** (**120_1** to **120_h**) includes a first switching element **156a**, a second switching element **156b**, and a third switching element **156c** disposed between the input terminal and the output terminal. The first switching element **156a**, the second switching element **156b**, and the third switching element **156c** are formed of transistors. The first switching element **156a**, the second switching element **156b**, and the third switching element **156c** are turned on and off by control signal lines **157a**, **157b**, **157c** connected to the gate of these transistors.

[0120] The first switching circuit **120_1** includes the first switching element **156a**, the second switching element **156b**, and the third switching element **156c** and is exclusively switched by the control signals of the control signal lines **157a**, **157b**, **157c**. That is, the first switching element **156a** is controlled by the control signal of the control signal line **157a**, the second switching element **156b** is controlled by the control signal of the control signal line **157b**, and the third switching element **156c** is controlled by the control signal of the control signal line **157c** so that any one of these switching elements is turned on and the other two switching elements are turned off. Such operations are similar for other switching circuits **120_2** to **120_h**.

[0121] The first connecting terminal **146a** is connected to the input terminal, and the plurality of data signal lines **108** (**S1-S3**) are connected to the output terminal, in the first switching circuit **120_1**. Specifically, the first switching element **156a** is connected between the first connecting terminal **146a** and the data signal line **108** (**S1**), the second switching element **156b** is connected between the first connecting terminal **146a** and the data signal line **108** (**S2**), and the third switching element **156c** is connected between the first connecting terminal **146a** and the data signal line **108** (**S3**), in the first switching circuit **120_1**. Other switching circuits **120_2** to **120_h** have similar circuitry. The first switching circuit **120_1** has the function of distributing the signals input to the first connecting terminal **146a** to a plurality of the data signal lines **108** (**S1-S3**) through the switching operation of the first switching element **156a**, the second switching element **156b**, and the third switching element **156c**. Other switching circuits **120_2** to **120_h** have similar functions.

[0122] The first sensor electrode **112_1** is disposed between the first switching circuit **120_1** and

the second switching circuit **120_2**. The first sensor electrode **112_1** is connected to the second connecting terminal **146b**. Other first sensor electrode **112_2** to **112_k** is also disposed between other switching circuit **120_2**, **120_h**.

[0123] The shield electrode **116** is disposed overlapping the area of the terminal part **122**. An end of the shield electrode **116** is located outside the first connecting terminal **146a** and the second connecting terminal **146b**. The first connecting terminal **146a** and the second connecting terminal **146b** are disposed on the upper side of the shield electrode **116**, across an insulating layer (not shown). The first connecting terminal **146a** and the second connecting terminal **146b** are disposed on the upper side of the shield electrode **116** to withstand the crimping process when connecting the flexible circuit board **126** and to prevent sinking, deformation, and peeling. Also, the first connecting terminal **146a** and the second connecting terminal **146b** are disposed on the upper side of the shield electrode **116** to prevent video signals from propagating as noise to the touch and fingerprint sensor **110**.

[0124] The first sensor electrodes **112_1** to **112_k** is disposed on the underlayer side of the shield electrode **116** across an insulating layer (not shown). To connect the first sensor electrode **112_1** to the wiring extending from the second connecting terminal **146b**, a first opening **158** is disposed in the shield electrode **116** and the first contact hole **159** extending through the insulating layer, not shown, inside the first opening **158**. The first sensor electrode **112_1** and the second connecting terminal **146b** are connected via the first contact hole **159** having a hole diameter smaller than the diameter of the first opening **158**.

[0125] The second drive circuit **128** includes the data signal line drive circuit block **132** and the touch and fingerprint sensor detection circuit block **134** (further including the scanning signal line drive circuit block **130**, not shown). The data signal line drive circuit blocks **132** include circuitry for controlling the operation of the switching circuits **120** (**120_1** to **120_h**). The arrangement of the respective circuit blocks in the second drive circuit **128** is optional, and the arrangement of the data signal line drive circuit blocks **132** and the touch and fingerprint sensor detection circuit blocks **134** may be replaced with the arrangement illustrated.

[0126] In the terminal part where the connecting terminals are arranged, if all the plurality of data signal lines and the plurality of first sensor electrodes are to be connected separately and independently at individual connecting terminals, the pitch of the connecting terminals becomes small. Generally, as the pitch of the connecting terminals in the terminal part becomes smaller, connection with the flexible circuit board becomes more difficult, resulting in defects and a lower manufacturing yield.

[0127] In contrast, the display device with the touch and fingerprint sensor **100** in the present embodiment has a reduced number of connecting terminals due to the provision of switching circuits **120** (**120_1** to **120_h**). That is, it is possible to connect the plurality of data signal lines **108** (for example, **S1** to **S3**) to one first connecting terminal **146a**, and reduce the number of connecting terminals, by providing the switching circuit **120**. Thus, the addition of the second connecting terminal **146b** connected to the first sensor electrode **112** to the terminal part **122** prevents a simple increase in the terminal number of connections and prevents a narrower pitch for the connecting terminal. As a result, defective connections with the flexible circuit board **126** can be prevented.

[0128] FIG. **6** shows an example in which the first switching element **156a**, the second switching element **156b**, and the third switching element **156c** constituting the switching circuits **120** (**120_1** to **120_h**) are configured with dual-gate transistors. The use of a dual-gate transistor as the first switching element **156a**, the second switching element **156b**, and the third switching element **156c** sharpens the rise and fall of the switching and can be operated even at high driving frequencies of the switching circuits **120** (**120_1** to **120_h**). This allows the switching circuits **120** (**120_1**-**120_h**) to operate synchronously with the frame frequency even when the frame frequency of the display device with the touch and fingerprint sensor **100** is high. In addition, it is possible to reduce the off-current (leakage current when the switch is off), which results in a reliable switching operation and

reduces power consumption, by using dual-gate transistors as the first switching element **156a**, the second switching element **156b**, and the third switching element **156c**.

[0129] FIG. 7 shows examples in which the end of the shield electrode **116** is disposed inside the terminal part **122**. The end of the shield electrode **116** is in the area between the terminal part **122** and the first opening **158** and the first connecting terminal **146a** and the second connecting terminal **146b** are located outside the shield electrode **116**. According to such structures, the parasitic capacitance between the first connecting terminal **146a** and the second connecting terminal **146b** and the shield electrode **116** can be reduced and power consumption can be reduced. In FIG. 7, the configuration other than the shield electrode **116** is the same as that shown in FIG. 5.

[0130] FIG. 5 shows the configuration when one first sensor electrode **112** is disposed for an array of one column of pixels **104**. The number of the first sensor electrodes **112** may be reduced even if the sensitivity of the fingerprint sensor is reduced to some acceptable degree. For example, the first sensor electrode **112** may be disposed for the array of two columns of pixels **104**. FIG. 8 shows an array of the switching circuit **120** and the first sensor electrode **112** in this case. As shown in FIG. 8, the switching circuit **120** can be disposed even if the number of the first sensor electrodes **112** is reduced, and the pitch of the connecting terminals of the terminal part **122** can be increased.

[0131] Although the pitches of the connecting terminal of the terminal part **122** are not uniformly disposed in FIG. 5, FIG. 6, FIG. 7, and FIG. 8, it is preferred that the pitches of the connecting terminal be uniformly disposed to further improve the yield of connecting the terminal part **122** to the flexible circuit board **126**.

1-4. Structures of Sensor Electrode

1-4-1. First Sensor Electrode

[0132] FIG. 9 shows an arrangement of the plurality of pixels **104** and the plurality of first sensor electrodes **112** and the plurality of second sensor electrodes **114**. FIG. 9 shows an example in which the plurality of pixels **104** include the first sub-pixel **105r** corresponding to red (R), the second sub-pixel **105g** corresponding to green (G), and the third sub-pixel **105b** corresponding to blue (B), wherein the sub-pixel corresponding to each color is arranged in stripes in the first direction (column direction). The first sensor electrodes **112** extending in the first direction (column direction) are arranged corresponding to the arrangement of the plurality of pixels **104** in the first direction (column direction), and the second sensor electrodes **114** extending in the second direction (row direction) are also arranged corresponding to the arrangement of the plurality of pixels **104** in the second direction (row direction).

[0133] To detect fingerprints, the first sensor electrode **112** must be disposed at a pitch of 25 μm to 120 μm , and the pitch range of 45 μm to 75 μm is most suitable. The second sensor electrode **114** also needs to be disposed at similar pitches. If the pitch of the first sensor electrode **112** and the second sensor electrode **114** is too large, the resolution is reduced, and fingerprints cannot be detected accurately. On the other hand, even if the pitch is less than 25 μm , there is no improvement in the accuracy of detecting fingerprints, and the number of sensor electrodes increases, resulting in an over-engineering.

[0134] Although not shown in FIG. 9, the data signal line is disposed corresponding to the first (column) array of first sub-pixel **105r**, the second sub-pixel **105g**, and the third sub-pixel **105b**. Accordingly, the first sensor electrode **112** is disposed in a ratio of one to three data signal lines. The pitch of the data signal line corresponding to the first sub-pixel **105r**, the second sub-pixel **105g**, and the third sub-pixel **105b** is, for example, 17 μm for a 5.5 inch, full high definition smartphone display panel. Accordingly, when the first sensor electrode **112** is disposed corresponding to the column orientation of each pixel **104**, the pitch of the first sensor electrode **112** is 51 μm . Referring now to FIG. 5, FIG. 6, and FIG. 7, since the first connecting terminal **146a** is located at a pitch of 51 μm and the second connecting terminal **146b** is located therebetween, the pitch of the connecting terminal in the terminal part **122** is 25.5 μm . With respect to the second sensor electrode **114**, the pitch of the scanning signal line corresponding to the second direction

(row direction) of the first sub-pixel **105r**, the second sub-pixel **105g**, and the third sub-pixel **105b** becomes 51 μm , and the pitch of the second sensor electrode **114** becomes 51 μm as well.

[0135] As a sensor for detecting fingerprints, it is considered that the pitch of the sensor electrode is about 50 μm from the viewpoint of resolution. The number of the first sensor electrode **112** may be reduced even when the sensitivity of the fingerprint sensor is reduced to some acceptable degree. For example, the first sensor electrode **112** may be disposed at intervals of one pixel. In this case, according to the above examples, the pitch of the first sensor electrode **112** is 102 μm , and the pitch of the connecting terminal in the terminal part **122** can be increased to about 34 μm .

[0136] FIG. **10** shows an example when the pitches of both sensor electrode are increased for the arrangement of the first sensor electrode **112** and the second sensor electrode **114** shown in FIG. **9**. That is, FIG. **10** shows an example in which one first sensor electrode **112** is disposed for two columns of arrays of pixels **104** in the column direction and one second sensor electrode **114** is disposed for two rows of arrays in the row direction. As described above, the pitches of the first sensor electrode **112** and the second sensor electrode **114** are about 100 μm , but fingerprints can be detected even in such pitches. In contrast to the arrangement of the first sensor electrode **112** shown in FIG. **10**, the arrangement of the connecting terminals in the switching circuit **120** and the terminal part **122** is as shown in FIG. **8**, allowing a wider pitch for the connecting terminals.

[0137] FIG. **11A** and FIG. **11B** shows an example of the first sensor electrode **112**. FIG. **11A** shows a plan view of the first sensor electrode **112**, and FIG. **11B** shows a corresponding cross-sectional view of the line A1-A2.

[0138] The first sensor electrode **112** has striped patterns extending along the first direction (column direction) in the display part **102**. The first sensor electrode **112** is formed of a first sensor electrode layer **204** with translucency. The first sensor electrode layer **204** is formed of, for example, a conductive metal oxide such as indium tin oxide (ITO), aluminum (Al) or gallium (Ga) doped zinc oxide (ZnO), indium zinc oxide (IZO), tin oxide (SnO.sub.2) or niobium (Nb) doped titanium oxide (TiO.sub.x), a transparent conductive film such as metal nitride or metal oxynitride such as titanium nitride (TiN.sub.x) or titanium oxynitride (TiON), or a conductive organic substance such as polyaniline or graphene. A width W1 of the first sensor electrode **112** is disposed so that it is wider than the width Wp of the sub-pixel **105**. Since the first sensor electrode layer **204** is disposed in accordance with the array of the sub-pixels **105** in the first direction (column direction), the first sensor electrode **112** is disposed so as to cover the entire sub-pixel **105**.

[0139] A first auxiliary electrode **205a** may be added to the first sensor electrode layer **204**. The first auxiliary electrode **205a** has thin linear patterns along the upper edges of the striped patterns of the first sensor electrode layer **204**. The first auxiliary electrode **205a** may also include a strip-like pattern connecting thin-linear patterns on both sides of the sub-pixel **105** arranged in a first direction (row direction) at spaced apart regions. The first auxiliary electrode **205a** may also include a strip-like pattern connecting thin-linear patterns on both sides of the sub-pixel **105** arranged in a first direction (row direction) at spaced apart regions. The first auxiliary electrode **205a** is formed of a lower resistivity material than the transparent conductive film material forming the first sensor electrode layer **204**. For example, the first auxiliary electrode **205a** is formed of a metal film such as aluminum (Al), a metal nitride such as titanium nitride (TiN), a metal silicide such as titanium silicide (TiSi.sub.x), or the like. The first auxiliary electrode **205a** formed of such conductive materials is formed of substantially the same width (thickness) as the data signal line **108** disposed in the display part **102** and is disposed in a position overlapping the data signal line **108**. The first auxiliary electrode **205a** contacting the first sensor electrode layer **204** can be disposed to reduce the resistivity of the first sensor electrode **112**.

[0140] Since the width W1 of the first sensor electrode layer **204** is greater than the width Wp of the sub-pixel **105**, the resistivity of the first sensor electrode **112** can be reduced without reducing the aperture ratio of the sub-pixel **105**. For example, for the 5.5 inch, full high definition smartphone display panel shown above, the width of the first sensor electrode **112** may be greater

than 17 μm (51 $\mu\text{m}/3$) and 20 μm . Also, the pitch L1 of the strip-like pattern of the first auxiliary electrode **205a** is preferably greater than the length Lp of the sub-pixel **105**. The pitch L1 of this strip-like pattern may be the same as the pitch of the scanning signal line. According to the preceding example, the pitch L1 may be 51 μm .

[0141] The width (thickness) of this strip-like pattern is formed in substantially the same width (thickness) as a scanning signal line **106** and is placed in a position overlapping the scanning signal line **106**. Such an arrangement allows a low resistivity of the first sensor electrode **112** without reducing the aperture ratio.

[0142] Thus, it is possible to lower the resistance of the first sensor electrode **112** by providing the first auxiliary electrode **205a** in the first sensor electrode layer **204**. Thereby, the sensitivity of the touch and fingerprint sensor part **110** can be prevented from decreasing and a drop in the response speed can be prevented.

[0143] FIG. **12A** and FIG. **12B** shows another example of the first sensor electrode **112**. FIG. **12A** shows a plan view of the first sensor electrode **112**, and FIG. **12B** shows a corresponding cross-sectional view of the line B1-B2.

[0144] A first auxiliary electrode **205b** is disposed in contact with the first sensor electrode layer **204**. . . . The first auxiliary electrode **205b** has a composite shape of a thin linear pattern disposed in the central portion of the first sensor electrode layer **204** and a strip-shaped pattern disposed in the area between the arrays of the sub-pixel **105**. The first auxiliary electrode **205b** is formed of a metal film, a metal nitride film, or a metal silicide film. The first auxiliary electrode **205b** of the configuration shown in FIG. **12A** and FIG. **12B** is formed of substantially the same width (thickness) as the data signal line **108** of the display part **102** and is disposed overlapping the data signal line **108**. The strip-like pattern of the first auxiliary electrode **205b** is formed of substantially the same width (thickness) as the scanning signal line **106** and is disposed to overlap the scanning signal line **106**. This type of first auxiliary electrode **205b** may also reduce the resistivity of the first sensor electrode **112**.

1-4-2. Second Sensor Electrode

[0145] FIG. **13A** shows a plan view of the second sensor electrode **114**. FIG. **13A** further shows the structures (first gate electrode **152**, second oxide semiconductor layer **180b**, second gate electrode **153**) of a portion of the select transistor **138** on the second sensor electrode **114** as dotted lines.

FIG. **13B** shows a corresponding cross-sectional structure of the line C1-C2 shown in FIG. **13A**.

[0146] The second sensor electrode **114** has striped patterns extending along the second direction (row direction) in the display part **102**. The second sensor electrode **114** traverses the display part **102** in the second direction (row direction) and is disposed so that both ends reach the peripheral area. The second sensor electrode **114** is formed of a second sensor electrode layer **206** with translucency. The second sensor electrode layer **206** is formed of a transparent conductive film similar to the first sensor electrode layer **204**.

[0147] The second sensor electrode **114** is disposed with a second auxiliary electrode **207**. The second auxiliary electrode **207** is disposed in contact with the second sensor electrode layer **206**. The second auxiliary electrode **207** is disposed along a longitudinal direction of the second sensor electrode layer **206**. The second auxiliary electrode **207** is formed of a metal film, a metal nitride film, or a metal silicide film. Similar to the first sensor electrode **112**, the second sensor electrode **114** is formed of the second sensor electrode layer **206** and the second auxiliary electrode **207** to reduce the resistivity.

[0148] FIG. **13B** shows the structures in which a first transparent resin layer **202a**, a second transparent resin layer **202b**, a third transparent resin layer **202c**, a fourth transparent resin layer **202d**, a first insulating layer **210**, and a second insulating layer **212** are laminated as the transparent resin substrate **200**. The second sensor electrode layer **206** is disposed between the second transparent resin layer **202b** and the third transparent-resin layer **202c**. The second auxiliary electrode **207** is disposed between the second sensor electrode layer **206** and the third transparent

resin layer **202c**. The shield electrode **116** is disposed on the third transparent resin layer **202c**. The fourth transparent resin layer **202d** is disposed on the shield electrode **116**. The first insulating layer **210** is disposed on the fourth transparent resin layer **202d**. A second oxide semiconductor layer **180b** is also disposed between the first insulating layer **210** and the second insulating layer **212**, and the second gate electrode **153** is disposed on the second insulating layer **212**.

[0149] A second light shielding layer **208b** is disposed on the lower layer side of the first gate electrode **152**. The second light shielding layer **208b** is formed of a conductive film consecutively formed from the second auxiliary electrode **207**. Alternatively, as shown in FIG. **13A**, the linear pattern of the second auxiliary electrode **207** extending in the second direction (row direction) has a convex pattern protruding in the area where the select transistor **138** is disposed. The second auxiliary electrode **207** having such patterns functions as the second light shielding layer **208b** for the sub-pixel **105**. The shape of the second light shielding layer **208b** protruding from the second auxiliary electrode **207** in a plan view is arbitrary and is not limited to the shape shown in FIG. **13A**.

[0150] The second auxiliary electrode **207** also functions as a scanning signal line (gate bus line) **106** of the display part **102**. The second gate electrode **153** is disposed on the second insulating layer **212**. The second gate electrodes **153** are separated and individually disposed for each sub-pixel **105**. The second gate electrode **153** is connected to the second auxiliary electrode **207** by the second insulating layer **212**, the first insulating layer **210**, the fourth transparent resin layer **202d**, and a third contact hole **163** through the third transparent resin layer **202c**. The shield electrode **116**, which is disposed between the third transparent resin layer **202c** and the fourth transparent resin layer **202d**, is disposed with a third opening **162** having a diameter $d1$ larger than the diameter $d2$ of the third contact hole **163**. The third contact hole **163** is disposed to pass through an area inside the third opening **162**.

[0151] The first gate electrode **152** is disposed connected to the shield electrode **116**. The first gate electrode **152** is secured to the same potential as the shield electrode **116**. The select transistor **138** is disposed with the first gate electrode **152** to which a constant potential is applied on the opposite side (back channel side) of the second gate electrode **153**, thereby preventing fluctuations in electrical characteristics.

[0152] A structure shown in FIG. **13A** and FIG. **13B** allows a thickness of the second insulating layer **212** to be thinned to 100 nm to 200 nm because the scanning signal lines **106** are disposed on the lower layer than the second oxide semiconductor layer **180b**. Since the second gate electrode **153** does not cross the data signal line **108**, even if the thickness of the second insulating layer **212** is reduced, both will not short-circuit. It is possible to obtain the select transistor **138** with excellent switching characteristics and fast response speed by thinning the second insulating layer **212**, which functions as the gate insulating layer.

[0153] FIG. **13A** shows only the select transistor **138** and the drive transistor **136** is omitted. However, the metallic layers forming the second auxiliary electrode **207** can also be used to dispose a light shielding layer for the drive transistor **136**.

[0154] FIG. **14A** and FIG. **14B** show an embodiment in which the second sensor electrode **114** differs from the structures shown in FIG. **13A** and FIG. **13B**. FIG. **14A** shows a plan view of the second sensor electrode **114**. FIG. **14A** further shows some of the structures (first gate electrode **152**, second oxide semiconductor layer **180b**, second gate electrode **153**, scanning signal line **106**) of the select transistor **138** disposed on the second sensor electrode **114**. FIG. **14B** shows the corresponding cross-sectional structure of the line C3-C4 shown in FIG. **14A**, and FIG. **14C** shows the corresponding cross-sectional structure of the line C5-C6 shown in FIG. **14A**.

[0155] The second sensor electrode **114** is formed of the second sensor electrode layer **206** and the second auxiliary electrode **207**. The second auxiliary electrode **207** has linear patterns extending longitudinally in the second sensor electrode **114** in the display part **102**. The second light shielding layer **208b** overlapping the second oxide semiconductor layer **180b** formed by the metal film

forming the second auxiliary electrode **207** is disposed above the second sensor electrode **114**.
[0156] The second gate electrode **153** and the scanning signal line **106** are disposed on the second insulating layer **212**. The second gate electrodes **153** are formed in consecutive patterns from the scanning signal line **106**. That is, the second gate electrode **153** and the scanning signal line **106** are formed of the same conductive layer. The second gate electrode **153** is disposed with the scanning signal line **106** coupled to each row of the sub-pixel **105**.

[0157] The scanning signal line **106** is connected to the second auxiliary electrode **207** in the peripheral area. A fourth opening **164** is disposed in the shield electrode **116** in the peripheral area. The scanning signal line **106** is disposed inside the fourth opening **164** and is connected to the second auxiliary electrode **207** by a fourth contact hole **165** having a diameter smaller than the diameter of the fourth opening **164**. The second light shielding layer **208b** may be separated from the second auxiliary electrode **207** as shown in the figure, or may be disposed sequentially from the second auxiliary electrode **207** as shown in FIG. **13B**.

[0158] It is possible to reduce wiring resistance by connecting the scanning signal line **106** to the second auxiliary electrode **207** in the peripheral area. In other words, the second auxiliary electrode **207** can be used as auxiliary wiring for the scanning signal line **106**.

[0159] Note that FIG. **14A** and FIG. **14C** show only the select transistor **138**, and the drive transistor **136** is omitted. The drive transistor **136** is similar in construction to the select transistor **138** and may be disposed with the second light shielding layer **208b** using the metal film forming the second auxiliary electrode **207**.

1-5. Partial Structure of Pixel and Sensor

[0160] FIG. **15** shows an example of a planar layout of the sub-pixel **105** (corresponding to each of the first sub-pixel **105r**, second sub-pixel **105g**, and third sub-pixel **105b**) shown in the equivalent circuit of FIG. **4**. Details of the stacked structures of the first sensor electrode **112** and the second sensor electrode **114**, and the EL element **142** are omitted in FIG. **15**.

[0161] As shown in FIG. **15**, the sub-pixel **105** includes the drive transistor **136**, the select transistor **138**, the capacitive element **140**, and the EL element **142**. Areas of the sub-pixel **105** are disposed with the scanning signal line **106a**, the data signal line **108**, the common electrodes **144a**, and the common wiring **144b**. The drive transistor **136** has a structure in which the first gate electrode **150** (lower layer side) and the second gate electrode **151** (upper layer side) are disposed sandwiched between a first oxide semiconductor layer **180a**. The select transistor **138** has a structure in which the first gate electrode **152** (lower layer side) and the second gate electrode **153** (upper layer side) are disposed between the second oxide semiconductor layer **180b**. A first light shielding layer **208a** is disposed on the lower side of the drive transistor **136** and the second light shielding layer **208b** is disposed on the lower side of the select transistor **138**. The first light shielding layer **208a** and the second light shielding layer **208b** are formed of the same conductive layer as the conductive layer forming the scanning signal line **106a**. The first light shielding layer **208a** and the second light shielding layer **208b** are formed in consecutive patterns from the scanning signal line **106a**.

[0162] The drive transistor **136** includes the first oxide semiconductor layer **180a**, a first metal oxide conductive layer **176a**, and a second metal oxide conductive layer **176b**. The first metal oxide conductive layer **176a** and the second metal oxide conductive layer **176b** are disposed in contact with the first oxide semiconductor layer **180a**. The first metal oxide conductive layer **176a** and the second metal oxide conductive layer **176b** include regions in which the ends are spaced apart and facing each other. The ends and separated apart regions are and overlap the first gate electrode **150**, the second gate electrode **151**, and the first oxide semiconductor layer **180a**. A channel of the drive transistor **136** is formed at a portion where the first metal oxide conductive layer **176a** and the second metal oxide conductive layer **176b** are separated apart.

[0163] The first metal oxide conductive layer **176a** is disposed in contact with a source wiring **170**. The source wiring **170** is connected to the common electrode **144a** via a fifth contact hole **166**. The

second metal oxide conductive layer **176b** is formed in contact with a first electrode **220** forming the EL element **142**. The second metal oxide conductive layer **176b** and the first electrode **220** are disposed in a continuous pattern.

[0164] The second metal oxide conductive layer **176b** is extended to the region of the EL element **142** to form the first electrode (cathode) **220**. The first oxide semiconductor layer **180a** extends into the region of the EL element **142** to form a first electron transport layer **222a**. The first electron transport layer **222a** is disposed over the first electrode **220**.

[0165] The select transistor **138** includes the second oxide semiconductor layer **180b**, a third metal oxide conductive layer **176c**, and a fourth metal oxide conductive layer **176d**. The third metal oxide conductive layer **176c** and the fourth metal oxide conductive layer **176d** are disposed in contact with the second oxide semiconductor layer **180b**. The third metal oxide conductive layer **176c** and the fourth metal oxide conductive layer **176d** include regions disposed so that the ends are spaced apart and opposite each other. The ends and separated apart regions overlap the first gate electrode **152**, the second gate electrode **153**, and the second oxide semiconductor layer **180b**. A channel of the select transistor **138** is formed in a portion where the third metal oxide conductive layer **176c** and the fourth metal oxide conductive layer **176d** are separated apart.

[0166] The third metal oxide conductive layer **176c** is disposed to include areas overlapping the data signal line **108**. The fourth metal oxide conductive layer **176d** is disposed in contact with a drain wiring **173**. The fourth metal oxide conductive layer **176d** and the drain wiring **173** are disposed to extend into the region of the capacitive element **140**.

[0167] The second gate electrode **153** of the select transistor **138** is individually disposed for each sub-pixel **105** and is connected to the scanning signal line **106a** (**207**) via the third contact hole **163**. The second gate electrode **151** of the drive transistor **136** is connected to the drain wiring **173** via a seventh contact hole **168**.

[0168] The capacitive element **140** is formed in the area where the drain wiring **173** and the fourth metal oxide conductive layer **176d** overlap the common wiring **144b**. An insulating layer is interposed between the drain wiring **173** and the fourth metal oxide conductive layer **176d** and the common wiring **144b** (not shown in FIG. **15**).

[0169] FIG. **16A** shows the cross-sectional structure of sub-pixel **105** corresponding to the line D1-D2 shown in FIG. **15**. FIG. **16B** shows the cross-sectional structure of the sub-pixel **105** corresponding to the line D3 and D4 shown in FIG. **15**. FIG. **16A** shows the cross-sectional structure of the drive transistor **136** and the EL element **142**, and FIG. **16B** shows the cross-sectional structure of the select transistor **138** and the capacitive element **140**.

[0170] The first sensor electrode **112** and the second sensor electrode **114** are disposed on the transparent resin substrate **200**. The drive transistor **136**, the select transistor **138**, the capacitive element **140**, and the EL element **142** are disposed on the transparent resin substrate **200**. The transparent resin substrate **200** has a plurality of transparent resin layer laminated structures. The transparent resin substrate **200** has structures in which the first transparent resin layer **202a**, the second transparent resin layer **202b**, and the third transparent resin layer **202c** are laminated. The first sensor electrode **112** is disposed between the first transparent resin layer **202a** and the second transparent resin layer **202b**, and the second sensor electrode **114** is disposed between the second transparent resin layer **202b** and the third transparent resin layer **202c**. The touch and fingerprint sensor **110** is disposed in an embedded state in the transparent resin substrate **200**.

[0171] The display device with the touch and fingerprint sensor **100** according to the present embodiment emits light emission of the plurality of pixels **104** (specifically, the EL element **142** arranged in each sub-pixel **105**) from the transparent resin substrate **200** side. The first sensor electrode **112** and the second sensor electrode **114** are disposed in an area overlapping the plurality of pixels **104** and are formed with a transparent conductive film to transmit light emitted from the plurality of pixels **104**. Alternatively, the first sensor electrode **112** and the second sensor electrode **114** may each have openings through which light passes according to the arrangement of the pixel

105. That is, the first sensor electrode **112** and the second sensor electrode **114** may be formed of a metal film, such as aluminum (Al), having a ladder-shaped pattern, such as the first auxiliary electrode **205a** shown in FIG. **11A** and FIG. **11B**, a metal nitride film, such as titanium nitride (TiN), a metal silicide film, such as titanium silicide (TiSi.sub.x), or the like.

[0172] The first transparent resin layer **202a**, the second transparent resin layer **202b**, the third transparent resin layer **202c**, and the fourth transparent resin layer **202d** have a thickness of 3 μm to 20 μm, preferably 10 μm to 15 μm. The transparent resin substrate **200** has flexibility due to the construction in which a transparent resin layer of such a film thickness is laminated. The display device with the touch and fingerprint sensor **100** has the transparent resin substrate **200** side as the sensing and display surface. When the first sensor electrode **112** and the second sensor electrode **114** are used as electrodes to detect fingerprints, the thickness of the first transparent resin layer **202a** is preferably thin. The first transparent resin layer **202a** and the second transparent resin layer **202b** may be disposed at a thickness of about 10 μm to 15 μm to obtain high sensitivity for detecting fingerprints. In order to form a contact hole, the second transparent resin layer **202b**, the third transparent resin layer **202c**, and the fourth transparent resin layer **202d** are preferably as thin as possible unless a pinhole is formed, but preferably have a thickness of actually 3 μm to 5 μm because of problems with increasing parasitic capacitance. Since the first transparent resin layer **202a** is a backbone layer of the transparent resin substrate **200**, it is preferred to have a thickness of about 20 μm to 50 μm.

[0173] The first shading layer **208a** overlapping the drive transistor **136** and the second shading layer **208b** overlapping the select transistor **138** are disposed on the second sensor electrode **114**. The first light shielding layer **208a** and the second light shielding layer **208b** are formed of a metal film, a metal nitride film, or a metal silicide film. The first light shielding layer **208a** and the second light shielding layer **208b** are disposed in the same layer as the scanning signal line **106a** (also the second auxiliary electrode **207**) disposed in the second sensor electrode **114** as shown in FIG. **15**.

[0174] The shield electrode **116** is disposed between the drive transistor **136**, the select transistor **138**, the capacitive element **140**, and the EL element **142** and the first sensor electrode **112** and the second sensor electrode **114**. The shield electrode **116** is disposed between the third transparent resin layer **202c** and the fourth transparent resin layer **202d**. The shield electrode **116** is disposed over the entire the display part **102**.

[0175] The shield electrode **116** is formed of a transparent conductive film. As the transparent conductive film, conductive metal oxides such as indium tin oxide (ITO), zinc oxide (ZnO), indium zinc oxide (IZO) and tin oxide (SnO.sub.2), metal nitrides such as titanium nitride (TiN.sub.x) and titanium oxynitride (TiON), and conductive organic materials such as polyaniline and graphene are used. Alternatively, the shield electrode **116** may be formed of a metallic material, such as aluminum, titanium, copper, or the like, and may have a construction in which openings are disposed to transmit light in accordance with the pixel arrangement. The common electrode **144a** and the common wiring **144b** are disposed in contact with the top surface of the shield electrode **116**. The common wiring **144b** is disposed to extend in the same direction as the scanning signal line **106a** extends. The common electrode **144a** and the common wiring **144b** are formed of a metal film such as aluminum (Al). The common electrodes **144a**, the common wiring **144b** and the shield electrode **116** are at the same potential and are applied to a constant potential. For example, the shield electrode **116** and the common electrodes **144a** and the common wiring **144b** are applied to a ground potential.

[0176] The first gate electrode **150** of the drive transistor **136** and the first gate electrode **152** of the select transistor **138** are disposed above the shield electrode **116**. The first gate electrode **150** and the first gate electrode **152** are formed on the same layer as the common electrode **144a** and the common wiring **144b**. The first gate electrode **150** and the first gate electrode **152** are formed of a metal film. The first gate electrode **150** and the first gate electrode **152** are disposed in contact with

the top surface of the shield electrode **116**. The first gate electrode **150** and the first gate electrode **152** are applied with the same potential as the shield electrode **116**.

[0177] The first sensor electrode **112** is a receiver electrode (Rx electrode) and the second sensor electrode **114** functions as the transmitter electrode (Tx electrode), in the touch and fingerprint sensor part **110**. When the touch and fingerprint sensor part **110** is driven, the second sensor electrode **114** is applied with a rectangular pulse voltage. An electric field generated by the rectangular pulse voltage applied to the second sensor electrode **114** is shielded by the shield electrode **116**. It is possible to drive the display part **102** and the touch and fingerprint sensor part **110** without mutual interference due to the electric field shielding effect of the shield electrode **116**. It is possible for the touch and fingerprint sensor section **110** to detect fingerprints with a high degree of accuracy because the influence of noise associated with driving the display part **102** is eliminated. In addition, the display part **102** can display images in a stable state without being affected by the touch and fingerprint sensor part **110**.

[0178] The fourth transparent resin layer **202d** is disposed on the shield electrode **116**. Since the first transparent resin layer **202a**, the second transparent resin layer **202b**, the third transparent resin layer **202c**, and the fourth transparent resin layer **202d** are formed by using the resin composition, irregularities due to the first sensor electrode **112**, the second sensor electrode **114**, the first gate electrode **150**, the first gate electrode **152**, and the common electrode **144a**, the common wiring **144b** can be embedded and the surface of the fourth transparent resin layer **202d** can be planarized.

[0179] As resinous materials forming the first transparent resin layer **202a**, the second transparent resin layer **202b**, the third transparent resin layer **202c**, and the fourth transparent resin layer **202d**, a transparent polyimide resin, a transparent polyethylene naphthalate resin, a transparent para-based polyamide resin, and the like are used. Since the transparent polyimide resin and the transparent polyethylene naphthalate resin have less gas barrier properties than the glass substrate, a gas barrier film formed by the silicon nitride film, or the like may be disposed. On the other hand, since the transparent para-polyamide resin has transparency, heat resistance, and gas barrier properties, it can be suitably used as a material to form the transparent resin substrate **200**. The first transparent resin layer **202a**, the second transparent resin layer **202b**, the third transparent resin layer **202c**, and the fourth transparent resin layer **202d** may be formed of the same resinous materials, or some or all layers may be formed of different resinous materials. For example, the fourth transparent resin layer **202d** can enhance the long-term reliability of the EL device **142** by using a rigid, gas-barrier transparent para-polyamide resin.

[0180] The transparent resin substrate **200** preferably has heat resistance from 150° C. to 400° C. When the maximum process temperature (heating temperature) when forming the drive transistor **136** and the select transistor **138** is 250° C. or lower, para-based polyamide resin can be used as the resin material. The use of para-based polyamide resin allows the transparent resin substrate **200** itself to have gas barrier properties. On the other hand, when the maximum process temperature (heating temperature) when forming the drive transistor **136** and the select transistor **138** is 250° C. or higher, it is preferable to use transparent polyimide resin as the material forming the transparent resin substrate **200** from the viewpoint of heat resistance.

[0181] In addition, the nanocellulose fiber (CNF) may be mixed with the transparent polyimide resin and the transparent para-based polyamide resin. The transparent polyimide resins and the transparent para-based polyamide resins with the nanocellulose fibers (CNF) are advantageous in that they improve stiffness, reduce shrinkage, and improve dimensional stability. Nanocellulose fibers (CNFs) may be mixed in at least one layer of the first transparent resin layer **202a**, the second transparent resin layer **202b**, the third transparent resin layer **202c**, and the fourth transparent resin layer **202d**, in order to improve the heat resistance of the transparent resin substrate **200**. The mixture ratio of nanocellulose fibers (CNF) to transparent polyimide resin and transparent para-polyamide resin is preferably between 1% and 10% by weight.

[0182] The drive transistor **136** shown in FIG. **16A** has a structure in which the first gate electrode

150, the first insulating layer **210**, the first oxide semiconductor layer **180a**, the second insulating layer **212**, and the second gate electrode **151** are stacked. The first gate electrode **150** is disposed to overlap the first oxide semiconductor layer **180a** via the first insulating layer **210**, and the second gate electrode **151** is disposed to overlap the first oxide semiconductor layer **180a** via the second insulating layer **212**. The first gate electrode **150**, the second gate electrode **151**, and the first oxide semiconductor layer **180a** have an overlapping region with each other, and a channel of the drive transistor **136** is formed in the overlapping region. The first gate electrode **150** is applied with the same potential as the shield electrode **116**, and a voltage based on the data signal (a voltage based on the video signal) is applied to the second gate electrode **151** in the drive transistor **136**.

[0183] The first metal oxide conductive layer **176a** and the second metal oxide conductive layer **176b** are disposed between the first insulating layer **210** and the first oxide semiconductor layer **180a**. The first metal oxide conductive layer **176a** and the second metal oxide conductive layer **176b** are disposed so that the first gate electrode **150** and the second gate electrode **151** are sandwiched from both sides in a plane view. The first metal oxide conductive layer **176a** and the second metal oxide conductive layer **176b** are disposed to contact the underside of the first oxide semiconductor layer **180a**. The drive transistor **136** has a drain region in which the second metal oxide conductive layer **176b** contacts the first oxide semiconductor layer **180a**, and a source region in which the first metal oxide conductive layer **176a** contacts the first oxide semiconductor layer **180a**.

[0184] The first oxide semiconductor layer **180a** is formed using a metal oxide semiconductor material. A quaternary metal oxide material, a ternary metal oxide material, a binary metal oxide material, and a monolithic metal oxide semiconductor material are used as a metal oxide semiconductor material. These metal oxide semiconductor materials may be single layer structures or may have laminated structures. The metal oxide semiconductor material may also be amorphous or crystalline.

[0185] In.sub.2O.sub.3—Ga.sub.2O.sub.3—SnO.sub.2—ZnO oxide materials can be used as quaternary oxide materials, In.sub.2O.sub.3—Ga.sub.2O.sub.3—SnO.sub.2 oxide materials, In.sub.2O.sub.3—Ga.sub.2O.sub.3—ZnO oxide materials, In.sub.2O.sub.3—SnO.sub.2—ZnO—ZnO oxide materials, In.sub.2O.sub.3—Al.sub.2O.sub.3—ZnO oxide materials, Ga.sub.2O.sub.3—SnO.sub.2—ZnO oxide materials, Ga.sub.2O.sub.3—Al.sub.2O.sub.3—ZnO oxide materials, SnO.sub.2—Al.sub.2O.sub.3—ZnO oxide materials, and Ga.sub.2O.sub.3—Al.sub.2O.sub.3—ZnO oxide materials can be used as ternary oxide materials, In.sub.2O.sub.3—ZnO oxide materials, SnO.sub.2—ZnO oxide materials, Al.sub.2O.sub.3—ZnO oxide materials, MgO—ZnO oxide materials, SnO.sub.2—MgO-based oxide materials, In.sub.2O.sub.3—MgO-based oxide materials can be used as binary oxide materials, In.sub.2O.sub.3-based metal oxide materials, SnO.sub.2-based metal oxide materials, and ZnO-based metal oxide materials can be used as unary oxide materials. Silicon (Si), nickel (Ni), tungsten (W), hafnium (Hf), titanium (Ti), and tantalum (Ta) may be contained in the above oxide semiconductor materials. The In—Ga—Zn—O oxide material shown above is an oxide material containing at least In, Ga, and Zn, and there is no restriction on its composition ratio. The above quaternary, ternary, binary, and unary oxide materials are not limited to those in which the oxides contained are of stoichiometric composition, and may be composed of oxide materials having compositions deviating from the stoichiometric composition. Such metal oxide semiconductor materials have a band gap of 3.0 eV or higher and are transparent to light in the visible light band.

[0186] The first metal oxide conductive layer **176a** and the second metal oxide conductive layer **176b** are formed of a conductive metal oxide material, a metal nitride material, or a metal acid nitride material. For example, indium tin oxide (ITO), zinc oxide (ZnO), indium zinc oxide (IZO), tin oxide (SnO.sub.2), and titanium oxide (TiNbO.sub.x) with niobium added are used as the conductive metal oxide material. Metal nitrides and metal nitrides having transparency and conductivity can also be used, such as titanium nitride (TiN.sub.x), titanium nitride acid (TiON).

[0187] The source electrode (first metal oxide conductive layer **176a**) of the drive transistor **136** is connected to the common electrode **144a**. The first metal oxide conductive layer **176a** is disposed to contact the common electrode **144a** through the fifth contact hole **166**. The source wiring **170** formed of a metal film is disposed above the first metal oxide conductive layer **176a**. The source wiring **170** is disposed extending into the region of the fifth contact hole **166**. The fifth contact hole **166** is formed through the first insulating layer **210** and the fourth transparent resin layer **202d**. The source wiring **170** and common electrode **144a** and common wiring **144b** are formed of a metallic material such as titanium (Ti), aluminum (Al), molybdenum (Mo), copper (Cu).

[0188] The first insulating layer **210**, for example, has structures in which a first silicon nitride film **214a** and a first silicon oxide film **215a** are laminated from the side of the fourth transparent resin layer **202d**. The second insulating layer **212**, for example, has structures in which a second silicon oxide film **215b** and a second silicon nitride film **214b** are laminated from the side of the first oxide semiconductor layer **180a**. The first oxide semiconductor layer **180a** is disposed in contact with the first silicon oxide film **215a** and the second silicon oxide film **215b**. The first oxide semiconductor layer **180a** is disposed with the upper and lower surfaces in contact with the silicon oxide film, thereby inhibiting the production of oxygen deficiency.

[0189] The first gate electrode **150** and second gate electrode **151** are formed from metallic materials such as aluminum (Al), molybdenum (Mo), tungsten (W), zirconium (Zr), and copper (Cu). Aluminum alloys such as aluminum-neodymium alloy (AlNd), aluminum-neodymium-nickel alloy (AlNdNi), aluminum-carbon-nickel alloy (AlCnNi), copper-nickel alloy (CuNi) can be used. For example, the first gate electrode **150** and the second gate electrode **151** are formed of aluminum (Al), molybdenum-tungsten (MoW) alloy, and molybdenum-titanium (MoTi) alloy.

[0190] The select transistor **138** has a structure in which the first gate electrode **152**, the first insulating layer **210**, the second oxide semiconductor layer **180b**, the second insulating layer **212**, and the second gate electrode **153** are stacked. A channel of the select transistor **138** is formed in the region where the second oxide semiconductor layer **180b** overlaps the first gate electrode **152** and the second gate electrode **153**. The first gate electrode **152** is disposed in contact with the shield electrode **116**.

[0191] The third metal oxide conductive layer **176c** and the fourth metal oxide conductive layer **176d** are disposed between the first insulating layer **210** and the second oxide semiconductor layer **180b**. The third metal oxide conductive layer **176c** and the fourth metal oxide conductive layer **176d** are disposed in contact with the lower surface of the second oxide semiconductor layer **180b** to function as the source region and the drain region. The third metal oxide conductive layer **176c** and the fourth metal oxide conductive layer **176d** are disposed to be sandwiched from both sides of the first gate electrode **152** and the second gate electrode **153** in a plane view.

[0192] A third metal oxide conductive layer **176c** is disposed in contact with the lower surface of the data signal line **108**. The data signal lines **108** are in direct contact with the third metal oxide conductive layer **176c**, which increases the contact area and reduces contact resistance compared to when they are connected via contact holes.

[0193] The drain wiring **173** is disposed in contact with the top surface of a fourth metal oxide conductive layer **176d**. The second oxide semiconductor layer **180b** is disposed to cover the top surface of the fourth metal oxide conductive layer **176d** and the drain wiring **173**. The drain wiring **173** is connected to the second gate electrode **151** of the drive transistor **136** via the seventh contact hole **168**.

[0194] The capacitive element **140** shown in FIG. **16B** is formed in the area where the drain wiring **173**, the fourth metal oxide conductive layer **176d**, the first insulating layer **210**, the fourth transparent resin layer **202d**, and the common wiring **144b** overlap. The fourth metal oxide conductive layer **176d** and the drain wiring **173** form one capacitance electrode, and the common wiring **144b** forms the other capacitance electrode. The capacitive element **140** is disposed between the drain electrode of the select transistor **138** and the common wiring **144b**.

[0195] The drive transistor **136** and the select transistor **138** are covered with a third insulating layer **216**. The third insulating layer **216** is formed of an organic resinous material such as an acrylic resin, a polyimide resin, an epoxy resin, a polysiloxane resin, or a polyamide resin. The third insulating layer **216** has function as a planarizing film that embeds the drive transistor **136** and the selective transistor **138** formed by these resin compositions. The third insulating layer **216** may be formed of an inorganic insulating film such as a silicon oxide film, a silicon nitride film, or the like.

[0196] As shown in FIG. **16A**, the EL element **142** has a structure in which the first electrode **220** corresponding to a cathode, the electron transport layer **222** (first electron transport layer **222a**, second electron transport layer **222b**), an electron injection layer **224**, a light emitting layer **226**, a hole transport layer **228**, a hole injection layer **230**, and a second electrode **232** corresponding to an anode are laminated from the side of the transparent resin substrate **200**. For convenience, the EL element may be referred to as an inverse stacked structure when it has a hole transport layer, a light emitting layer, an electron transport layer, or a structure laminated from the anode side, such as a cathode, and vice versa. The EL element **142** shown in FIG. **16A** is classified into an inverse stack structure.

[0197] The first electrode **220** is continuous from the first metal oxide conductive layer **176a**, and the first electron transport layer **222a** is continuous from the first oxide semiconductor layer **180a**. The drive transistor **136** and the EL element **142** are connected without using a contact hole by having such a structure. The first electrode **220** corresponding to the cathode is formed of the same metal oxide conductive material as the first metal oxide conductive layer **176a**. The first electron transport layer **222a** is formed of the same oxide semiconductor material as the first oxide semiconductor layer **180a**.

[0198] A third opening **234** is arranged in the third insulating layer **216** and the second insulating layer **212** in the region where the EL element **142** is formed. The third opening **234** exposes a top surface of the first electron transport layer **222a**, which is disposed on the upper layer side of the first electrode **220**. The second electron transport layer **222b**, the electron injection layer **224**, the light emitting layer **226**, the hole transport layer **228**, the hole injection layer **230**, and the second electrode **232** as the anode are stacked on top of the first electron transport layer **222a**. The area where these layers and the first electrode **220** overlap is the light emission area of the EL element **142**.

[0199] The first electron transport layer **222a**, which is formed of the same layer as the first oxide semiconductor layer **180a**, is disposed on the upper layer of the first electrode **220**. The first electron transport layer **222a** is preferably transparent to visible light with a band gap of 3.0 eV or higher. The second electron transport layer **222b** is formed of a metal oxide material containing one or more elements selected from indium oxide, zinc oxide, gallium (Ga) oxide, tin (Sn) oxide, magnesium (Mg) oxide, silicon (Si) oxide, hafnium (Hf) oxide, tantalum (Ta) oxide and niobium (Nb) oxide. These metal-oxide materials have a band gap of more than 3.0 eV and are translucent to visible light. The second electron transport layer **222b** is formed with a film thickness of 50 nm to 1000 nm. The second electron transport layer **222b** having a thickness in this range prevents a short circuit between the first electrode **220** and the second electrode **232**.

[0200] A carrier concentration of the second electron transport layer **222b** should be less than one-tenth of the carrier concentration of the first electron transport layer **222a**, preferably less than one-hundredth of the carrier concentration of the first electron transport layer **222a**. Specifically, the carrier concentration of the second electron transport layer **222b** is $10^{13}/\text{cm}^3$ to $10^{17}/\text{cm}^3$, while that of the first electron transport layer **222a** is in the range of $10^{15}/\text{cm}^3$ to $10^{19}/\text{cm}^3$, the difference in carrier concentration between both should be more than one order of magnitude, preferably more than two orders of magnitude, as described above. The first electron transport layer **222a** has a carrier concentration in the range of $10^{15}/\text{cm}^3$ to $10^{19}/\text{cm}^3$, which reduces the resistance loss in the connection

between the drive transistor **136** and the EL element **142** and prevents the drive voltage from increasing. When the carrier concentration of the second electron transport layer **222b** is $10^{20}/\text{cm}^3$ or higher, the excited state in the light emitting layer **226** is deactivated and the luminous efficiency decreases. On the other hand, when the carrier concentration of the second electron transport layer **222b** is less than $10^{13}/\text{cm}^3$, the carriers supplied to the light emitting layer **226** are reduced and sufficient brightness cannot be obtained. It is possible to prevent the drive voltage from increasing and increase the luminous efficiency of the EL element **142** by providing the first electron transport layer **222a** in contact with the second electron transport layer **222b** and by differentiating the carrier concentration of the two layers.

[0201] The carrier concentration of the first electron transport layer **222a** and the second electron transport layer **222b** can be controlled by the concentration of oxygen deficiency in the oxide semiconductor. The oxygen defects in an oxide semiconductor act as donors. Increasing the oxygen deficiency density of an oxide semiconductor increases the carrier concentration, while decreasing the oxygen deficiency density decreases the carrier concentration. The oxygen deficiency of an oxide semiconductor can be increased by, for example, the addition of hydrogen, and decreased by the supply of oxygen.

[0202] The electron injection layer is used in the EL device to reduce the energy barrier for injecting electrons from the cathode to the electron transport layer. The electron injection layer **224** is disposed to facilitate the injection of electrons from the second electron transport layer **222b** to the light emitting layer **226**. The electron injection layer **224** is disposed between the second electron transport layer **222b** and the light emitting layer **226**.

[0203] The electron injection layer **224** uses a material with a low work function. The electronic injection layer **224** is formed of an oxide semiconductor material including, for example, $\text{Ca}_{12}\text{Al}_7\text{O}_{23}$ electride, $\text{Mg}_{0.3}\text{Zn}_{0.7}\text{O}$, $\text{Zn}_{0.7}\text{Si}_{0.3}\text{O}_x$. The electron injection layer **224** is formed at a thickness of 1 nm to 100 nm. It is possible to increase the number of electrons injected from the second electron transport layer **222b** to the light emitting layer **226** by using this type of electron injection layer **224**, thereby increasing the luminous efficiency.

[0204] The light emitting layer **226** is applicable to various light emission materials. The light emitting layer **226** is formed using, for example, a fluorescent material, a phosphorescent material that emits phosphorescence, and a thermally activated delayed fluorescence (TADF) material. The light emitting layer **226** is made of materials with different emission colors corresponding to the plurality of sub-pixels **105** included in the pixel **104**. To make the light emitting layer **226** a white light emitting layer, a structure in which a blue light emitting layer and a yellow light emitting layer are stacked is used. The light emitting layer **226** can be made by vapor deposition, a transfer method, a spin-coating method, a spray-coating method, a gravure printing method, or other methods. The film thickness of the light emitting layer **226** may be selected as needed, but for example, it is formed in the range of 10 nm to 100 nm.

[0205] The hole transport layer **228** is formed, for example, of an arylamine compound, an amine compound comprising a carbazole group, and an amine compound comprising a fluorene derivative. The hole transport layer **228** is formed by vapor deposition, a coating method, or the like. The hole transport layer **228** is formed of a thickness between 10 nm and 500 nm. When hole injection layer **230** is formed, the hole transport layer **228** may be omitted.

[0206] The hole injection layer **230** is formed of metal oxides such as molybdenum oxide, vanadium oxide, ruthenium oxide, tungsten oxide, manganese oxide, and the like. The hole infusion layer **230** is also formed of materials such as phthalocyanine (H_2Pc), copper (II) phthalocyanine (CuPc), and hexaazatriphenylene hexacarbonitrile ($\text{HAT}(\text{CN})_6$), and the like. The hole injection layer **230** is formed at a thickness of 1 nm to 10 nm.

[0207] The second electrode **232** corresponding to the anode is preferably formed of a material having a work function of 4.0 eV or more. The second electrode **232** is formed of a conductive

metal oxide such as, for example, indium tin (ITO), indium zinc (IZO), tungsten oxide (WOx) and indium oxide containing zinc (ZnO) oxide (IWZO). Since the EL element **142** is a bottom emission type, the second electrode **232** preferably has a light reflective surface. Since the conductive metal oxide has light transmittance as described above, it is preferable to form a light reflection surface by laminating a metal film such as aluminum (Al) or silver (Ag).

[0208] Although omitted in FIG. **16A** and FIG. **16B**, passivation membranes may be disposed on the EL element **142** to block the penetration of oxygen and moisture.

[0209] Thus, the sub-pixel **105** according to the present embodiment has a configuration in which the n-channel drive transistor **136** and the EL element **142** are connected. The EL element **142** is a bottom emission type and is structured to emit light toward shield electrode **116**. Since the electron transport layer and the electron injection layer are formed of an inorganic metal oxide semiconductor material, the EL element **142** has a structure that prevents the deterioration of the light emission characteristics due to moisture (H.sub.2O) or oxygen (O.sub.2).

[0210] FIG. **17** shows a plan view showing another configuration of the sub-pixel **105**. The sub-pixel **105** shown in FIG. **17** has structures in which the second gate electrode **153** of the select transistor **138** and the scanning signal line **106a** are formed of the same conductive layer. The second auxiliary electrode **207** is disposed on the second sensor electrode **114** (FIG. **17** omits the patterns of the second sensor electrode **114** and only the second auxiliary electrode **207** is shown). The first light shielding layer **208a** and the second light shielding layer **208b** are formed of the same metallic film as the second auxiliary electrode **207** and are disposed on the second sensor electrode **114**.

[0211] FIG. **18** shows a planar layout of the sub-pixel **105** and shows a different configuration of connections between the drive transistor **136** and the common electrode **144a** with respect to the sub-pixel **105** shown in FIG. **15**. FIG. **19A** also shows a cross-sectional structure corresponding to the line D5-D6 shown in FIG. **18**, and FIG. **19B** shows a cross-sectional structure corresponding to the line D7-D8.

[0212] As shown in FIG. **18** and FIG. **19A**, the source wiring **170** of the drive transistor **136** is connected to the common electrode **144a** by a connecting wiring **172** formed of the same conductive layer as the second gate electrode **151**. The connecting wiring **172** is connected to the source wiring **170** by a contact hole **171** formed in the second insulating layer **212** and is connected to the common electrode **144a** by a contact hole **166** formed in the second insulating layer **212**, the first insulating layer **210**, and the fourth transparent resin layer **202d**. Such connecting structures may also realize the first sub-pixel **105r**, the second sub-pixel **105g**, and the third sub-pixel **105b** shown in the equivalent circuitry of FIG. **4**.

[0213] FIG. **20** shows a planar layout of sub-pixel **105** and shows a different configuration of connections between the select transistor **138** and the data signal line **108** with respect to the sub-pixel **105** shown in FIG. **18**. FIG. **21A** also shows a cross-sectional structure corresponding to the line D9-D10 shown in FIG. **20**, and FIG. **21B** shows a cross-sectional structure corresponding to the line D11-D12.

[0214] As shown in FIG. **20** and FIG. **21B**, a source electrode **174** of the select transistor **138** is connected to the data signal line **108** formed of the same conductive layer as the second gate electrode **153**. The data signal line **108** is disposed on the second insulating layer **212** and is connected to the source electrode **174** via a ninth contact hole **175**. The scanning signal line **106a** is disposed below the first insulating layer **210**. Accordingly, even when the second insulating layer **212** is thin, even when the data signal line **108** disposed on the same layer as the second gate electrode **153** is disposed to intersect the scanning signal line **106a**, short circuits at the intersection can be prevented.

1-6. Sealing Structure

[0215] FIG. **22A** shows an exemplary configuration of connections between the first sensor electrode **112** and a drawer wiring **147**. The drawer wiring **147** is a wiring that connects the first

sensor electrode **112** to the second connecting terminal **146b**. The first sensor electrode **112** is connected to the drawer wiring **147** in the outer area of the display part **102**. The drawer wiring **147** is disposed on the fourth transparent resin layer **202d** as well as the second connecting terminal **146b**. Similar to the construction shown in FIG. 5, the shield electrode **116** is disposed extending below the second connecting terminal **146b**. The second connecting terminal **146b** is disposed on the upper side of the shield electrode **116** to withstand the crimping process when connecting the flexible circuit board **126** and to prevent recess, deformation, and peeling of the second connecting terminal **146b**.

[0216] The shield electrode **116** has the first opening **158**. The first contact hole **159** with a hole diameter smaller than the diameter of the first opening **158** is disposed in this portion. The first contact hole **159** passes through the fourth transparent resin layer **202d**, the third transparent resin layer **202c**, and the second transparent resin layer **202b** to expose a top surface of the first sensor electrode **112**. The drawer wiring **147** extends from the second connecting terminal **146b** to the first contact hole **159** and is connected to the first sensor electrode **112**.

[0217] The first insulating layer **210**, the second insulating layer **212**, and the third insulating layer **216** are disposed on the fourth transparent resin layer **202d**. The second electrode **232** is disposed on the third insulating layer **216**. FIG. 22A and FIG. 22B show a structure in which a sealing layer **236** is disposed on the upper side of the second electrode **232**. The sealing layer **236** has a variety of structures, but has a structure in which, for example, a silicon nitride carbon film **237a**, a silicon nitride film **238**, and a silicon carbon nitride film **237b** are laminated is preferred.

[0218] The drawer wiring **147** is extended outward (toward the edge of the transparent resin substrate **200**) from the area covered by the third insulating layer **216** and the sealing layer **236**, and is connected to the second connecting terminal part **146b**. The drawer wiring **147** and the second connecting terminal **146b** are formed in the same conductive layer and in one continuous pattern.

[0219] FIG. 22A shows the transparent resin substrate **200** with a dividing region **240** in the area near the edge of the transparent resin substrate **200**. The transparent resin substrate **200** is disposed on a support substrate, which is not shown in the figure, during the manufacturing process, and is divided at the dividing region **240** when it is broken into individual panels. The dividing region **240** is formed with a continuous aperture groove that surrounds the display panel. The aperture grooves are formed, for example, by laser processing. The transparent resin substrate **200** is peeled off from the support substrate by a laser ablation process after forming the dividing region **240**.

[0220] FIG. 22B shows a configuration in which the shield electrode **116** does not extend to an area of the second connecting terminal **146b**, as shown in FIG. 7. Preferably, the first insulating layer **210** is disposed below the drawer wiring **147** and the second connecting terminal **146b**. The drawer wiring **147** is connected to the first sensor electrode **112** by the first contact hole **159** that passes through the first insulating layer **210**, the fourth transparent resin layer **202d**, the third transparent resin layer **202c**, and the second transparent resin layer **202b**.

[0221] Even if the shield electrode **116** is not disposed on the underside of the second connecting terminal **146b**, the first insulating layer **210** can be disposed to withstand the crimping process when connecting the flexible circuit board **126**, and to prevent sinking, deformation, and peeling of the second connecting terminal **146b**. Although not shown in the figure, the same advantageous effect can be obtained even if both the first insulating layer **210** and the shield electrode **116** are disposed on the lower side of the second connecting terminal **146b**. Although not shown in FIG. 22A and FIG. 22B, the structure of the first connecting terminal **146a** in the terminal part is also similar to that of the second connecting terminal **146b**, and the same advantageous effect can be achieved.

[0222] FIG. 23A and FIG. 23B show a different configuration of the second insulating layer **212** from FIG. 22A and FIG. 22B. The explanation of FIG. 23A and FIG. 23B will focus on the parts that differ from FIG. 22A and FIG. 22B.

[0223] FIG. 23A shows a structure in which the shield electrode **116** is disposed under the second

connecting terminal **146b** and the second insulating layer **212** is disposed over the drawer wiring **147**. The second insulating layer **212** covers the top and sides of the drawer wiring **147** and is disposed in contact with the fourth transparent resin layer **202d** in the area where the drawer wiring **147** is not disposed, which is not shown in the figure. The second insulating layer **212** is disposed extending outside of the third insulating layer **216** (on the side of the second connecting terminal **146b**). The second insulating layer **212** has an area outside the third insulating layer **216** in contact with the sealing layer **236**.

[0224] The second insulating layer **212** and the sealing layer **236** include an insulating film formed of an inorganic insulating material. Such a second insulating layer **212** and the sealing layer **236** may be disposed in contact with the outside of the third insulating layer **216** to improve the sealing performance. As shown in FIG. **16A**, layers forming the EL elements **142** are disposed on the third insulating layer **216**. The third insulating layer **216** in contact with the EL element **142** is sandwiched between the second insulating layer **212** and the sealing layer **236**, and the edge of the third insulating layer **216** is located inside the outer edge of the second insulating layer **212** and the sealing layer **236** to improve the ability to prevent degradation of the EL element **142**. Furthermore, since the second insulating layer **212** functions as a protective film for the drawer wiring **147**, deterioration and damage to the wiring can be prevented. The other structure is similar to FIG. **22A**, and the same advantageous effects can be obtained.

[0225] FIG. **23B** has a structure in which the first insulating layer **210** is disposed under the second connecting terminal **146b** and the second insulating layer **212** is disposed over the drawer wiring **147**. This structure can also improve sealing performance in the same way as the structure shown in FIG. **23A**. The other structure is similar to FIG. **22B**, and the same advantageous effect can be obtained. Although not shown in FIG. **23B**, the same advantageous effect can be obtained even if both the first insulating layer **210** and the shield electrode **116** are disposed on the lower side of the second connecting terminal **146b**.

[0226] FIG. **24A** and FIG. **24B** show a different configuration of the first insulating layer **210** and the second insulating layer **212** from FIG. **23A** and FIG. **23B**. The explanation of FIG. **24A** and FIG. **24B** will focus on the parts that differ from FIG. **23A** and FIG. **23B**.

[0227] FIG. **24A** and FIG. **24B** have a structure in which the shield electrode **116** is disposed under the second connecting terminal **146b**, and the first insulating layer **210** and the second insulating layer **212** are disposed under the drawer wiring **147** and the second connecting terminal **146b**. Since the first insulating layer **210** and the second insulating layer **212** are disposed on the entire underside of the second connecting terminal **146b**, the second connecting terminal **146b** can withstand the crimping process when connecting the flexible circuit board **126**, and the resistance to sinking, deformation, and peeling of the second connecting terminal **146b** can be further enhanced.

[0228] The sealing layer **236** has an area outside the third insulating layer **216** where it contacts the drawer wiring **147** and also contacts the second insulating layer **212** (not shown), which enhances sealing performance and prevents degradation of the EL element **142**.

[0229] FIG. **25A** and FIG. **25B** show an aspect in which the configuration of the drawer wiring **147** is different from that of FIG. **22A** and FIG. **22B**. The difference between FIG. **25A** and FIG. **25B** is in the presence or absence of the shield electrode **116** beneath the second connecting terminal **146b**. The description of FIG. **25A** and FIG. **25B** will be described with respect to portions that differ from FIG. **22A** and FIG. **22B**.

[0230] As shown in FIG. **25A** and FIG. **25B**, the connection structure of the first sensor electrode **112** and the second connecting terminal **146b** has a structure connected by a plurality of contact holes and a plurality of drawer wirings. Specifically, a contact hole **169a** is formed in the second transparent resin layer **202b**, and a first drawer wiring **147a** is connected to the first sensor electrode **112**, a contact hole **169b** is formed in the third transparent resin layer **202c**, and a second drawer wiring **147b** is connected to the first drawer wiring **147a**, a contact hole **169c** is formed in

the fourth transparent resin layer **202d**, and a third drawer wiring **147c** is connected to the second drawer wiring **147b**.

[0231] The contact hole **169a** connecting the first drawer wiring **147a** to the first sensor electrode **112** and the contact hole **169b** connecting the second drawer wiring **147b** to the first drawer wiring **147a** are in different positions. The contact hole **169b** connecting the second drawer wiring **147b** to the first wiring **147a** and the contact hole **169c** connecting the third drawer wiring **147c** to the second wiring **147b** are in different positions. Thus, it is possible to make the depth of each contact hole shallower by shifting the positions of the plurality of contact holes, and the connection of the drawer wirings can be formed securely.

[0232] The configuration shown in FIG. 25A and FIG. 25B can be applied to the configuration shown in FIG. 23A and FIG. 23B, FIG. 24A and FIG. 24B.

1-7. Flexible Circuit Board and Integrated Circuit

[0233] FIG. 26 shows a configuration of the transparent resin substrate **200** on which the display part **102** and the touch and fingerprint sensor part **110** are disposed, and the flexible circuit board **126** on which the second drive circuit **128** is disposed.

[0234] The flexible circuit board **126** includes the third connecting terminal **148a**, the fourth connecting terminal **148b**, a fifth connecting terminal **148c**, a sixth connecting terminal **149**, and wiring groups **129a**, **129b** on a film substrate **127**. The wiring group **129** connects between the third connecting terminals **148** to the fifth connecting terminals **148c** and the second drive circuit **128**, and between the second drive circuit **128** and the sixth connecting terminal **149**. The third connecting terminal **148a** is connected to the first connecting terminal **146a** on the transparent resin board **200**, the fourth connecting terminal **148b** is connected to the second connecting terminal **146b** on the transparent resin board **200**, the fifth connecting terminal **148c** is connected to the connecting terminal connected to the first drive circuit **118** on the transparent resin board **200**. The sixth connecting terminal **149** is connected to an external circuit that drives the display device with the touch and fingerprint sensor **100**.

[0235] The second drive circuit **128** is a composite integrated circuit that integrates the first scanning signal line drive circuit block, the data signal line drive circuit block, and the touch and fingerprint sensor detection circuit block, as shown in FIG. 5. The second drive circuit **128** is mounted on the surface of the film substrate **127** by COF (Chip on Film).

[0236] FIG. 27 shows a plan view of the flexible circuit board **126**. The flexible circuit board **126** includes the third connecting terminal **148a**, the fourth connecting terminal **148b**, and the fifth connecting terminal **148c** on the first side of the film substrate **127** formed of polyimide or the like, and the sixth connecting terminal **149** on the second side opposite the first side. The second drive circuit **128** is mounted in the central area of the film substrate **127**. FIG. 27 shows the area in which the second drive circuit **128** is implemented in dotted lines.

[0237] The wiring group **129a** is disposed in the areas between the third connecting terminal **148a**, the fourth connecting terminal **148b**, and the fifth connecting terminal **148c** and the second drive circuit **128**. The wiring group **129b** is disposed in the area between the second drive circuit **128** and the sixth connecting terminal **149**. Each of the wirings of the wiring group **129b** is drawn from the sixth connecting terminal **149** to the area where pads **135** of the second drive circuit **128** is located. Each of the wirings of the wiring group **129a** is drawn from the area where the pads **135** of the second drive circuit **128** is located to the third connecting terminal **148a**, the fourth connecting terminal **148b**, and the fifth connecting terminal **148c**.

[0238] The pads **135** of the second drive circuit **128** are disposed corresponding to the functional blocks. That is, the pads **135** of the second drive circuit **128** are disposed in the areas of the respective circuit blocks corresponding to the scanning signal line drive circuit block **130**, the data signal line drive circuit block **132**, and the touch and fingerprint sensor detection circuit block **134**. The connection between the respective wirings of the wiring groups **129a**, **129b** and the pads **135** is connected by a conductive material. The connections between the third connecting terminal **148a**,

the fourth connecting terminal **148b**, and the fifth connecting terminal **148c** and the connecting terminal on the transparent resin substrate **200** are also connected by a conductive material. [0239] FIG. **28** shows a configuration of the switching circuit **120** and the first sensor electrode **112** shown in FIG. **7** in which the flexible circuit board **126** is overlaid on the terminal part **122** and the connecting terminal is connected with conductive materials. The flexible circuit board **126** is disposed with the third connecting terminal **148a** and the fourth connecting terminal **148b** corresponding to the first connecting terminal **146a** and the second connecting terminal **146b** disposed in the terminal part **122** of the transparent resin substrate **200**. As described with reference to FIG. **5**, the first connecting terminal **146a** is connected to the switching circuit **120** and the second connecting terminal **146b** is connected to the first sensor electrode **112** via the first contact hole **159** disposed in the inner area of the first opening **158** of the shield electrode **116**.

[0240] The first connecting terminal **146a** and the third connecting terminal **148a** and the second connecting terminal **146b** are spaced apart from the fourth connecting terminal **148b**. At least one conductive particle **242** is disposed between the first connecting terminal **146a** and the third connecting terminal **148a**. The at least one conductive particle **242** is held in a pressurized deformed condition between the first connecting terminal **146a** and the third connecting terminal **148a**. The at least one conductive particle **242** contacts the first connecting terminal **146a** and the third connecting terminal **148a**. The first connecting terminal **146a** and the third connecting terminal **148a** are electrically connected by the at least one conductive particle **242**. Similarly, conductive particles are disposed between the second connecting terminal **146b** and the fourth connecting terminal **148b**. Preferably, the at least one conductive particle **242** includes a plurality of conductive particles.

[0241] The plurality of conductive particles **242** are disposed over the first connecting terminal **146a** (or the third connecting terminal **148a**) in a dispersed in a resin **244**. When the first connecting terminal **146a** and the third connecting terminal **148a** are facing to each other in this state, and the distance between them is narrowed to the extent that the plurality of conductive particles **242** are pressurized and deformed, the plurality of conductive particles **242** can protrude from the resin **244** and make direct contact with the first connecting terminal **146a** and the third connecting terminal **148a**.

[0242] It is preferred that the plurality of conductive particles **242** be included in the resin **244**. For example, it is preferred that 2 to 7 conductive particles **242** be included in a single region of resin **244**. As a result, the plurality of conductive particles **242** will be interposed between the first connecting terminal **146a** and the third connecting terminal **148a** to ensure electrical connection.

[0243] As shown in FIG. **28**, the resin **244** containing the plurality of conductive particles **242** is disposed between the first connecting terminal **146a** and the third connecting terminal **148a** in a plurality of positions. In other words, the conductive particles **242** are disposed between the first connecting terminal **146a** and the third connecting terminal **148a** in a controlled number and position. It is possible to reliably form an electrical connection and prevent a short circuit with the adjacent connecting terminal, by arranging the plurality of conductive particles **242** in a controlled number and position in the area between the first connecting terminal **146a** and the third connecting terminal **148a**. This configuration is effective when the pitch of the connecting terminals is narrower.

[0244] It is preferable that a diameter of the plurality of conductive particles **242** be in the range of 2 μm to 10 μm or less. Such a size can prevent short circuits between adjacent connecting terminals even when the pitch of the connecting terminals is 30 μm or less. As shown in FIG. **28**, when the resin **244** containing a plurality of conductive particles **242** is disposed in several discrete locations between connecting terminals, the spacing between the discrete locations should be 5 μm or more. This arrangement can prevent the resin **244** containing the plurality of conductive particles **242** from protruding from the first connecting terminal **146a** and the third connecting terminal **148a**, and the spacing between the first connecting terminal **146a** and the third connecting terminal **148a**

can be kept constant.

[0245] The structure, shape, and material of the conductive particle **242** are not limited, but may be, for example, a particle nucleus of a highly hard resin material coated with a rubber-like elastic resin, or a particle nucleus of a highly hard inorganic material coated with a rubber-like inorganic elastic material, which is coated with a metal such as nickel (Ni), copper (Cu), or gold (Au). The shape of the conductive particle **242** is not limited to a sphere, but may be oblong or a composite.

[0246] The resin **244** is a curable resin material. The curable resin material includes radical polymerization type resin materials. The radical polymerization type resin material is preferably a (meth)acrylic monomer or (meth)acrylate oligomer, and those bonded in the ester type are more preferred. The (Meth)acrylate oligomers can be those having at least one or more of a (meth)acryloyl group, such as epoxy acrylate, urethane acrylate, polyester acrylate, polybutadiene acrylate, polyol acrylate, polyether acrylate, silicone resin acrylate, and melamine acrylate can be used. It can be either monofunctional or multifunctional, but more preferably contains multifunctional monomers or oligomers. The curable resin material may be composed of two or more of (meth)acrylate monomers and (meth)acrylate oligomers.

[0247] Although not shown, a second resin may be disposed around the resin **244**. The second resin is a curable resin material. Fluorene acrylate can be used as the curable resin material. As the curable resin material, an ene compound having two or more functional groups selected from the group consisting of allyl ether groups, vinyl ether groups, acrylate groups, and methacrylate groups in a molecule or an ene compound that is a mixture of two or more of the above ene compounds, or an ene/thiol curable resin containing a thiol compound having two or more thiol groups in one molecule which is obtained by an oxidative compound treatment may also be used.

[0248] The resin **244** and the second resin further contain a photo-curing initiator component. The photo-curing initiator component is a photo-radical initiator, which can be any compound that generates radicals when irradiated with ultraviolet or visible light. For example, acetophenone initiators, benzoin ether initiators, benzophenone initiators, alpha-diketone initiators, and thioxanthone initiators can be used as UV radical initiators.

[0249] The resin **244** containing the plurality of conductive particles **242** can be provided over the first connecting terminal **146a** (or the third connecting terminal **148a**) by a printing method. The offset printing method is used as the printing method. Since the resin **244** corresponding to the ink contains the plurality of conductive particles **242**, it is preferable to use a pad printing method that uses an intaglio plate in the offset printing method.

[0250] Since the resin **244** containing the plurality of conductive particles **242** is placed on the first connecting terminal **146a** (or the third connecting terminal **148a**) using a printing method to connect the flexible circuit board **126** to the transparent resin substrate **200**, the connection can be made accurately even if the connecting terminals are finer and narrower in pitch. The display device with the touch and fingerprint sensor **100** of the present embodiment increases the number of connecting terminals for taking out sensor signals due to the finer first sensor electrode **112** of the touch and fingerprint sensor part **110**. As shown in FIG. **26**, even when the terminal part **122** has a narrower pitch by including in the same array the connecting terminals for inputting signals for displaying images on the display part **102** and the connecting terminals for the touch and fingerprint sensor part **110**, it is possible to form an electrical connection by attaching the flexible circuit board **126** to the terminal part **122** with the resin **244** containing the plurality of conductive particles **242**.

[0251] FIG. **29** shows a configuration of the switching circuit **120** and the first sensor electrode **112** shown in FIG. **8**, with the flexible circuit board **126** overlaid on the terminal part **122** and the connecting terminals connected with a conductive material. FIG. **29** shows a configuration in which one first sensor electrode **112** is disposed for an array of two columns of pixels **104**. Therefore, the first connecting terminal **146a**, which is disposed in the terminal part **122** and connected to the switching circuit **120**, and the third connecting terminal **148a**, which is disposed

on the flexible circuit board **126**, are disposed close together. It is possible to prevent short circuits between adjacent terminals even with this arrangement of connecting terminals by using the plurality of conductive particles **242** dispersed in a controlled number in the resin **244** when connecting the first connecting terminal **146a** and the third connecting terminal **148a**.

[0252] FIG. **30** shows an example in which the second drive circuit **128** is composed of the composite integrated circuit in which multiple functions are integrated. The display device with the touch and fingerprint sensor **100** is not limited to this example, and as shown in FIG. **30**, a driver IC **125a** that drives the display part **102** and a driver IC **125b** that drives the touch and fingerprint sensor are formed in separate IC chips and mounted on the flexible circuit board **126**, and they may be mounted on the flexible circuit board **126**.

[0253] FIG. **31** shows a plan view of the flexible circuit board **126** on which the driver IC **125a** that drives the display part **102** and the driver IC **125b** that drives the touch and fingerprint sensors are mounted. The wiring from which the signal of the first sensor electrode **112** is output passes through the region of the driver IC **125a** that drives the display part and is arranged to reach the driver IC **125b** that drives the touch and fingerprint sensors. The wiring connecting the driver IC **125a** that drives the display part to the sixth connecting terminal **149** is arranged to pass through the region of the driver IC **125b** that drives the touch and fingerprint sensors and reach the sixth connecting terminal **149**.

[0254] The driver IC **125a** that drives the display part may be partitioned into the scanning signal line drive circuit block **130** and the data signal line drive circuit block **132**. In this embodiment, the first drive circuit **118** serves as the scanning signal line drive circuit and the drive circuit for the second sensor electrode **114**, as shown in FIG. **2**. To the first drive circuit **118**, signals to drive the scanning signal lines are output from the driver IC **125a** that drives the display part, and signals to control the drive of the second sensor electrode are output from the driver IC **125b** that drives the touch and fingerprint sensors.

[0255] As shown in FIG. **30** and FIG. **31**, it is possible to mount two driver ICs on the flexible circuit board **126** by changing the wiring structure, even if the driver IC that drives the display part and the driver IC that drives the touch and fingerprint sensor part are provided separately.

[0256] The display device with a touch and fingerprint sensor according to present embodiment can suppress the increase of connecting terminals even when a touch and fingerprint sensor part is disposed by connecting the data signal line to the switching circuit. In other words, it is possible to connect the data signal line to the switching circuit to suppress the increase in the number of connecting terminals even when the first sensor electrode (receiver electrode) is densely arranged. As a result, connection failures with the flexible circuit board can be reduced at the terminal part.

[0257] According to the display device with a touch and fingerprint sensor according to the present embodiment, the scanning signal line of the display part **102** can be used together as an auxiliary electrode to reduce the resistance of the second sensor electrode, by connecting the second sensor electrode (transmitter electrode) of the touch and fingerprint sensor part **110** and the scanning signal line of the display part **102**. In addition, a short circuit between the data signal line and the scanning signal line can be prevented even if the second gate insulating layer is thin, and the drive performance of the transistor (thin film transistor) can be increased, by making the scanning signal line contact the second sensor electrode and connecting the second gate electrode to the scanning signal line via a contact hole. Furthermore, the light shielding layer for the transistor can be formed with said metal layer, by forming the scanning signal lines with a metal layer in contact with the second sensor electrode.

Second Embodiment

[0258] FIG. **32** shows the display device with the touch and fingerprint sensor **100**, which includes the display unit **102** with the plurality of pixels **104**, the touch and fingerprint sensor **110** with the first sensor electrode **112** and the second sensor electrode **114**, the first drive circuit **118**, the switching circuit **120**, the terminal part **122**, and the flexible circuit board **126**. The first drive

circuit **118** includes the scanning signal line drive circuit **118a** that outputs scanning signals to the scanning signal lines and scan signals to the second sensor electrode **114**, and an output switching circuit **118b** that switches the connection between the scanning lines and the second sensor electrode **114**.

[0259] The second drive circuit **128** may be formed by a composite integrated circuit in which circuit blocks having different functions are integrated as in the first embodiment. The control signals for the scanning signal line drive circuit **118a** and the output switching circuit **118b** are output from the scanning signal line drive circuit block **130**.

[0260] FIG. **33** shows an example of the output switching circuit **118b** corresponding to the arrangement of the second sensor electrode **114** shown in FIG. **9**. The output switching circuit **118b** includes a first switching element **141_1** connected to the scanning signal line (G_1) and a second switching element **145_1** connected to the second sensor electrode **114** (SC_1), for the output of the first drive circuit **118**. The first switching element **141_1** and the second switching element **145_1** are connected in parallel. The first switching elements **141_1** to **141_n** are disposed for the scanning signal lines (G_1 to G_n) and the second switching elements **145_1** to **145_n** are disposed for the second sensor electrodes **114** (SC_1 to SC_n). The first switching element **141_1** and the second switching element **145_1** are formed by transistors, and the gates which control on/off are connected to a first output switching signal line **143a** and a second output switching signal line **143b**. The first output switching signal line **143a** and the second output switching signal line **143b** are connected to the second drive circuit **128**, and their on-off is controlled by the control signal output from the scanning signal line drive circuit block **130**.

[0261] The first switching elements **141_1** to **141_n** are turned on by the control signal on the first output switching signal line **143a** and the second switching elements **145_1** to **145_n** are turned off by the control signal on the second output switching signal line **143b**, and scanning signals are sequentially output to the scanning signal lines (G_1 to G_n), in a display period. The first switching elements **141_1** to **141_n** are turned off by the control signal on the first output switching signal line **143a** and the second switching elements **145_1** to **145_n** are turned on by the control signal on the second output switching signal line **143b**, and the scan signals are sequentially output to the second sensor electrodes **114** (SC_1 to SC_n), in the sensing period. Thus, the first drive circuit **118** switches the scanning signal lines (G_1 to G_n) and the second sensor electrodes **114** (SC_1 to SC_n) by means of the first switching elements **141_1** to **141_n** and the second switching elements **145_1** to **145_n**, thus the scanning signal line drive circuit that drives the display part **102** and the scanning circuit of the touch and fingerprint sensor part **110** can be shared.

[0262] FIG. **34** shows a configuration of the switching circuit **118b** corresponding to the arrangement of the second sensor electrodes **114** shown in FIG. **10**. The configuration shown in FIG. **10** has one second sensor electrode **114** for two rows of pixels **104**, so the number of second sensor electrodes **114** is half the number of scanning signal lines. Therefore, the output switching circuit **118b** has a circuit in which the first switching element **141_1** connected to the scanning signal line (G_1) and the second switching element **145_1** connected to the second sensor electrode **114** (SC_1) are arranged in parallel to the output of the first drive circuit **118**, and a circuit in which only the first switching element **141_2** connected to the second scanning signal line (G_2). The configuration of the switching circuit **118b** shown in FIG. **34** can similarly switch the scanning signal lines (G_1 to G_n) and the second sensor electrodes **114** (SC_1 to SC_(n+1)/2) to drive the display unit **100** with touch and fingerprint sensors.

[0263] The display device with a touch and fingerprint sensor shown in FIG. **32** is similar to the display device with a touch and fingerprint sensor described in the first embodiment, except for the different configuration of the first drive circuit **118**, and the same advantageous effects can be obtained.

Third Embodiment

[0264] This embodiment shows an example of a display device with a touch and fingerprint sensor

that differs from the first embodiment in the configuration of the drive circuit that outputs scanning and scan signals. In the following description, details will focus on the parts that differ from the first embodiment.

[0265] FIG. 35 shows the display device with the touch and fingerprint sensor **100**, which has the display part **102** with the plurality of pixels **104** arranged, the touch and fingerprint sensor part **110** disposed with the first sensor electrode **112** and the second sensor electrode **114**, the first drive circuit **118**, the switching circuit **120**, the terminal part **122**, and the flexible circuit board **126**. The first drive circuit **118** is divided into two circuit blocks including a scanning signal line drive circuit **118c**, which outputs scanning signals to the scanning signal lines, and a scan circuit **118d**, which outputs scan signals to the second sensor electrode **114**.

[0266] The second drive circuit **128** may be formed by a composite integrated circuit in which circuit blocks with different functions are integrated as in the first embodiment. The control signals to the scanning signal line drive circuit **118c** of the display part **102** and the scanning circuit **118d** of the touch and fingerprint sensor **110** are output from the scanning signal line drive circuit block **130**.

[0267] The display device with the touch and fingerprint sensor **100** shown in FIG. 35 can simultaneously display images and perform touch and fingerprint sensor sensing by having the scanning signal line drive circuit **118c** and the scan circuit **118d** formed by two independent circuit blocks.

[0268] FIG. 36A shows a plan view of the second sensor electrode **114** corresponding to the configuration shown in FIG. 35. FIG. 36B also shows the scanning signal line **106** and the select transistor **138** above the second sensor electrode **114** as dotted lines. FIG. 36B shows a cross-sectional structure corresponding to the line C7-C8 shown in FIG. 36A, and FIG. 36C shows a cross-sectional structure corresponding to the line C9-C10.

[0269] As shown in FIG. 36A, the second sensor electrode **114** is configured with the second sensor electrode layer **206** and the second auxiliary electrode **207**. As shown in FIG. 36B, the fourth transparent resin layer **202D**, the first insulating layer **210**, and the second insulating layer **212** are disposed between the second sensor electrode **114** and the scanning signal line **106**, and both are insulated. According to this wiring structure, the scan signal to the second sensor electrode **114** and the scanning signal to the scanning signal line **106** can be input simultaneously. In other words, the display device with the touch and fingerprint sensor **100** can detect fingerprints while displaying an image.

[0270] FIG. 37 shows a timing chart for the display device with the touch and fingerprint sensor **100** shown in FIG. 35. As shown in FIG. 37, the display device with the touch and fingerprint sensor **100** of the present embodiment has a display period and a sensing period that appear at the same time. The display device with the touch and fingerprint sensor **100** of the present embodiment has the scanning signal line drive circuit **118c** of the display part **102** and the scanning circuit **118d** of the touch and fingerprint sensor **110** in independent circuit blocks in the first drive circuit **118**, and the data signal line drive circuit block **132** and the touch and fingerprint sensor detection circuit block **134** are disposed in independent circuit blocks in the second drive circuit **128**, therefore, it is possible to perform image display and sensing at the same time.

[0271] According to the display device with the touch and fingerprint sensor **100** according to the present embodiment, for example, a touch or a fingerprint can be sensed while displaying a moving image. The other configuration is the same as the display device with a touch and fingerprint sensor in the first embodiment and can have the same advantageous effect.

Fourth Embodiment

[0272] This embodiment describes an example in which a portion of the transparent resin substrate **200** is replaced with ultra-thin tempered glass (UTG) for the display device with the touch and fingerprint sensor **100** shown in the first embodiment.

[0273] FIG. 38 shows the display device with the touch and fingerprint sensor **100** in which ultra-

thin tempered glass is used as a part of the transparent resin substrate **200**. Specifically, the transparent resin substrate **200** of the present embodiment has ultra-thin tempered glass applied to the first transparent resin layer **202a** in the structure of the transparent resin substrate **200** shown in FIG. **16A** and FIG. **16B**. The thickness of the ultra-thin tempered glass is 25 μm to 50 μm , for example, 30 μm . As shown in FIG. **38**, the transparent resin substrate **200** is processed into a round shape with four corners having a radius (R) of 2 mm to 5 mm to prevent breakage. The ultra-thin tempered glass is bendable, and the display device with the touch and fingerprint sensor **100** using such a transparent resin substrate **200** can be applied to electronic devices (for example, smartphones, tablet terminals) in which the display screen can be folded. The configuration of the present embodiment can be applied to the display device with touch and fingerprint sensors shown in the second and third embodiments.

Fifth Embodiment

[0274] This embodiment shows an example of a display device with a touch and fingerprint sensor that has a mounting method using Chip On Plastic (COP) as the mounting method for the drive circuit.

[0275] FIG. **39** shows the display device with the touch and fingerprint sensor **100** in which ultra-thin tempered glass is used as part of the transparent resin substrate **200**. The display part **102**, the touch and fingerprint sensor **110**, the first drive circuit **118**, the switching circuit **120**, the terminal part **122**, and the transparent resin substrate **200** are similar to those shown in the fourth embodiment. On the other hand, this embodiment differs in that the second drive circuit **128** is mounted on the transparent resin substrate **200**.

[0276] Similar to the transparent resin substrate shown in the fourth embodiment, the transparent resin substrate **200** in the present embodiment is processed into a round shape with a radius (R) of 2 mm to 5 mm for the four corners. When ultra-thin tempered glass is used for the transparent resin substrate **200**, this corner shape prevents breakage of the four corners in the assembly process and improves the yield rate.

[0277] FIG. **40** shows a cross-sectional structure of an area where the second drive circuit **128** is mounted and the terminal part **122**. The second drive circuit **128** includes a first pad **135a** and a second pad **135b**. The first pad **135a** is connected to the first connecting terminal **146a** via the plurality of conductive particles **242**, and the second pad **135b** is connected to the second connecting terminal **146b** via the plurality of conductive particles **242**. The second drive circuit **128** can be mounted on the transparent resin substrate **200** by using a non-heated room temperature pressure mounting technique. The plurality of conductive particles **242** are dispersed in the resin **244**, details of which are described in detail in the description of FIG. **28**.

[0278] The terminal part **122** is disposed outside the region where the second drive circuit **128** is mounted. FIG. **40** shows a structure in which the shield electrode **116** and the first insulating layer **210** extend from the region in which the second drive circuit **128** is mounted to the region of the terminal part **122**. With such a structure, it is possible to increase the rigidity of the area where the second drive circuit **128** is mounted, and to prevent the deformation and peeling of the connecting terminal. Thereby, the yield of the process of connecting the second drive circuit **128** can be improved. It is even more desirable to use a rigid para-polyamide resin for the fourth transparent resin layer **202d**.

[0279] As shown in FIG. **39** and FIG. **40**, the display device with touch and fingerprint sensor **100** can also be realized by mounting the second drive circuit **128** on the transparent resin substrate **200** by CPO. The display device with the touch and fingerprint sensor **100** according to the present embodiment eliminates the flexible circuit board by mounting the second drive circuit **128** on the transparent resin board **200**, thereby reducing the number of parts and the manufacturing process.

Sixth Embodiment

[0280] This embodiment shows a configuration of the display device with the touch and fingerprint sensor **100** in which the circuit configuration of the pixel **104** is different from that of the first

embodiment.

[0281] FIG. 41 shows an example of the equivalent circuit of the pixel 104 and an example of the pixel circuit of the voltage writing method. As described in the first embodiment, the pixel 104 includes the first sub-pixel 105r, the second sub-pixel 105g, and the third sub-pixel 105b, FIG. 41 shows the configuration of the first sub-pixel 105r and the second sub-pixel 105g in detail. The pixel 104 has a stripe configuration of columns of first sub-pixel 105r, columns of second sub-pixel 105g, and columns of third sub-pixel 105b.

[0282] The first sub-pixel 105r includes a drive transistor 136r, a select transistor 138r, a capacitive element 140r, and an EL element 142r, and the second sub-pixel 105g includes a drive transistor 136g, a select transistor 138g, a capacitive element 140g, and an EL element 142g. A second gate electrode is connected to the scanning signal line 106 (GBn) and a source is connected to the data signal line 108 (Dm) for the select transistor 138r of the first sub-pixel 105r. A second gate electrode is connected to the scanning signal line 136 (GAn) and a source is connected to the data signal line 108 (Dm+1) for the select transistor 138g of the second sub-pixel 105g. A second gate electrode is connected to the scanning signal line 136 (GBn) and a source is connected to the data signal line 108 (Dm+1) of the select transistor 138b of the third sub-pixel 105b. Thus, the pixel circuit of the present embodiment has a configuration in which the second gate electrodes of the select transistors of adjacent sub-pixels are connected to different scanning signal lines and the source is connected to the same data signal line. The pixel 104 is arranged so that the common wiring 144 is shared by the column Lr of the first sub-pixel 105r and the column Lg of the second sub-pixel 105g.

[0283] FIG. 42 shows a timing chart for driving the pixel 104 shown in FIG. 41. FIG. 42 shows that the scanning signal on scanning signal line 106 (GAn) transitions from a low level (L level) to a high level (H level) at time t-1, and select transistor 138g turns on, synchronized with this timing, a data signal is input to the data signal line 108 (Dm+1) and data is written to the second sub-pixel 105g, at time to, the scanning signal transitions to L level and the select transistor 138g turns off, and at the same time, the scanning signal on the scanning signal line 106 (GBn) transitions from low (L level) to high (H level) at time to and the select transistors 138r, 138b turn on, synchronized with this timing, data signals are input to the data signal lines 108 (Dm), 108 (Dm+1), and data is written to the first sub-pixel 105r and the third sub-pixel 105b, and at time t1, the scanning signal transitions to the L level and the select transistor 138r and the select transistor 138b are turned off.

[0284] In this way, the select transistors of adjacent sub-pixels (the first sub-pixel 105r and the second sub-pixel 105g, the second sub-pixel 105g and the third sub-pixel 105b) are connected to different scanning signal lines, so that adjacent sub-pixels (for example, the second and the third sub-pixels 105b) can share data signal lines 108 (Dm+1) and data can be written at different timings respectively. This configuration of the pixel circuit allows the number of data signal lines to be reduced. In other words, the number of connecting terminals in the terminal part 122 can be reduced.

[0285] FIG. 43 shows an example of an equivalent circuit of the pixel 104, which is an example of a pixel circuit with a current write method. The pixel 104 includes the first sub-pixel 105r, the second sub-pixel 105g, and the third sub-pixel 105b, FIG. 43 shows the configuration of the first sub-pixel 105r and the second sub-pixel 105g in detail.

[0286] The first sub-pixel 105r includes a first transistor 138r (select transistor), a second transistor 139r, a drive transistor 136r, a light emission control transistor 137r, a capacitive element 140r and the EL element 142r. Second gate electrodes of the first transistor 138r and the second transistor 139r are connected to the scanning signal line 106 (GBn), and sources are connected to the data signal line 108 (Dm), respectively. The drain of the first transistor 138r is connected to a second gate electrode of the drive transistor 136 and the capacitive element 140, and is used to control the timing for writing data signals. The second transistor 139r is connected to the drain of the drive

transistor **136** and its on/off operation is controlled at the same timing as the first transistor **138r** to compensate for the threshold voltage of the drive transistor **136r**. The light emission control transistor **137r** is connected in series between the EL element **142r** and the drive transistor **136r**, and its second gate is connected to a second scanning signal line **107** (En) to control the timing of light emission of the EL element **142r**. The second sub-pixel **105g** has a similar configuration. [0287] A second capacitive element **274r** may be disposed between the second scanning signal line **107** and the drain of the first transistor **138r**. It is possible to suppress the voltage of capacitive element **140r** from fluctuating by ΔV_{gd} due to the change in the gate-to-drain capacitance C_{gd} when the first transistor **138r** falls down by providing the second capacitive element **274r**.

[0288] In addition, there is a column of the third sub-pixel **105b**, which is not shown in the figure, the row of the third sub-pixel **105b** has the same configuration as the row Lr of the first sub-pixel **105r**, a source of each of the first transistor and the second transistor is connected to the data signal line **108** (Dm+1), the second gate electrode of each of the first transistor and the second transistor is connected to the scanning signal line **106** (GBn), a second gate electrode of the light emission control transistor is connected to the second scanning signal line **107** (En).

[0289] FIG. **44** shows a timing chart for driving the pixel **104** shown in FIG. **43**. FIG. **44** shows the operation that the scanning signal of the scanning signal line **106** (GAn) transitions from low level (L level) to high level (H level) at time t_0 , and the first transistor **138g** and a second transistor **139g** are turned on, synchronized with this timing, a data signal is input to the data signal line **108** (Dm+1) and data is written to the second sub-pixel **105g**, and the operation to compensate the threshold voltage of the drive transistor **136g** is also performed. FIG. **44** also shows the operation that at time t_1 , the scanning signal of scanning signal line **106** (GAn) transitions to L level and the first transistor **138g** and the second transistor **139g** turn off, at the same time, the scanning signal of scanning signal line **106** (GBn) transitions from low level (L level) to high level (H level) at time t_1 , and the first transistor **138r** and the second transistor **139r** turn on, and synchronized with this timing, a data signal is input to the data signal line **108** (Dm) to write data in the first sub-pixel **108r** and compensate for the threshold voltage of the drive transistor **136r**. During such a data writing period, the second scan signal line **107** (En) is at L level and the light emission control transistors **137r**, **137g** are off.

[0290] When the data writing period ends, it transitions to the emission period. That is, the second scan signal line **107** transitions from the L level to the H level, the emission signal is input, and the emission control transistors **137r**, **137g** are turned on. As a result, in the first sub-pixel **105r** and the second sub-pixel **108g**, a current corresponding to the drain current of the drive transistors **136r**, **136g** flows to the EL elements **142r**, **142g** to emit light.

[0291] The number of data signal lines **108** can be reduced by having the select transistors of adjacent sub-pixels (first sub-pixel **105r** and second sub-pixel **105g**) connected to different scanning signal lines, thus reducing the number of connecting terminals in terminal part **122**.

[0292] FIG. **47** shows the arrangement of the data signal lines **108** and the common wiring **144** shown in FIG. **41** and FIG. **43**. The data signal lines **108** are disposed on an upper layer than the fourth transparent resin layer **202d**, whereas the common wiring **144** is disposed between the third transparent resin layer **202c** and the fourth transparent resin layer **202d**, and in contact with the shield electrode **116**. While the shield electrode **116** is formed of a transparent conductive film, the common wiring **144** is formed of a metal film. The common wiring **144** is disposed in a stripe pattern extending from one end of the shield electrode **116** to the other end, thereby reducing the resistance of the shield electrode **116**.

[0293] FIG. **46** shows the display device with the touch and fingerprint sensor **100** in which ultra-thin tempered glass is used as part of the transparent resin substrate **200**. The display device with the touch and fingerprint sensor **100** shown in FIG. **46** has the same configuration as that shown in FIG. **39**, except that the switching circuit **120** is not provided and the configuration of the third connecting terminal **148a** and the second scanning signal line drive circuit **118e** is different.

[0294] The third connecting terminal **148a** in the second drive circuit **128**, which is provided in the data signal line drive circuit block **132**, is connected to the data signal line **108**, and data signals are output to each pixel **104** in the display part **102** without any switching circuit. As shown in FIG. **41** and FIG. **43**, the number of data signal lines **108** is arranged to be shared by adjacent pixel rows, so the number of third connecting terminals **148a** is reduced compared to the conventional method.

[0295] FIG. **45** shows details of the connection between the transparent resin substrate **200** and the second drive circuit **128**. The transparent resin substrate **200** is disposed with the first connecting terminal **146a** and the second connecting terminal **146b**. The first connecting terminal **146a** is connected to the data signal line **108**, and the second connecting terminal **146b** is connected to the first sensor electrode **112**. A third connecting terminal **148a** of the second drive circuit **128** is connected to the first connecting terminal **146a**, and a fourth terminal **148b** is connected to the second connecting terminal **146b**. The plurality of conductive particles **242** dispersed in the resin **244** are used for the connections. The details of the connection structure are the same as those shown in FIG. **28**.

[0296] According to the present embodiment, when the display part **102** has a configuration in which pixels corresponding to each color are arranged in stripes, the number of data signal lines **108** can be reduced by having a pixel circuit in which adjacent pixel columns share data signal lines **108**, thereby, the number of connecting terminals can be reduced without using the switching circuit **120**.

Seventh Embodiment

[0297] This embodiment shows an example of the layout of each element constituting the pixel **104** of the voltage writing method shown in FIG. **43**.

[0298] FIG. **48** shows an example of the layout of the first sub-pixel **105r** and the second sub-pixel **105g**. The first sub-pixel **105r** has the first transistor **138r**, the second transistor **139r**, the drive transistor **136r**, the light emission control transistor **137r**, and the capacitive element **140r**, and the second sub-pixel **105g** has the first transistor **138g**, the second transistor **139g**, the drive transistor **136g**, the light emission control transistor **137g**, and the capacitive element **140g**. Each layer consisting of the EL elements **142r**, **142g** is omitted. The first sensor electrode **112** and the second sensor electrode **114** are also omitted.

[0299] Focusing on the first sub-pixel **105r**, the first transistor **138r** is stacked with the first oxide semiconductor layer **180a**, a third metal oxide conductive layer **176c** forming the source, a fourth metal oxide conductive layer **176d** forming the drain, and the first scanning signal line **106** (GBn), the second gate electrode **153** formed of a transparent conductive layer extending to the region of the first transistor **138r** is stacked through the second insulating layer **212**, which is not shown in the figure, the first gate electrode **152** formed by the shield electrode **116** is also stacked through the first insulating layer **210**, which is not shown in the figure. The first gate electrode **152** is disposed on the lower layer and the second gate electrode **153** is disposed on the upper layer with respect to the first oxide semiconductor layer **180a**.

[0300] The second transistor **139r** has the same configuration as the first transistor **138r**, with the fifth metal oxide conductive layer **176e** forming the drain connected to the second metal oxide conductive layer **176a** forming the drive transistor **136r**.

[0301] The drive transistor **136r** has a structure in which the second gate electrode **151** on the same layer as the second gate electrode **153** is disposed to cover the first oxide semiconductor layer **180a**, the first metal oxide conductive layer **176a**, and the second metal oxide conductive layer **176b**. The capacitive element **140r** is formed in the region where the second gate electrode **151** and the second metal oxide conductive layer **176b** overlap.

[0302] The light emission control transistor **137r** has a stacked structure of the first oxide semiconductor layer **180a**, the sixth metal oxide conductive layer **176f**, which is connected to the first metal oxide conductive layer **176a**, the seventh metal oxide conductive layer **176g** disposed with a gap in this conductive layer, a second gate electrode **268** formed in a region overlapping

these two metal oxide conductive layers and forming the second scanning signal line **107** (En) and overlapping the region of the light emission control transistor **137r**, and a first gate electrode (**266**) formed by the shield electrode **116**, which is not shown in the figure. The EL element **142r**, not shown in the figure, is connected to the light emission control transistor **137r** through an eighth contact hole **264**.

[0303] The second sub-pixel **105g** has a similar configuration, with the layout of the first sub-pixel **105r** inverted around the common wiring **144** and further inverted in the vertical direction.

[0304] FIG. **49** shows a partial cross-sectional structure of the first sub-pixel **105r**, mainly showing the cross-sectional structure of the light emission control transistor **137r**, the capacitive element **140r**, and the EL element **142r** described in FIG. **48**. As shown in FIG. **49**, the light emission control transistor **137r** has the sixth metal oxide conductive layer **176f** and the second metal oxide conductive layer **176g** between the first insulating layer **210** and the first oxide semiconductor layer **180a**, the first gate electrode **248** is formed in the same layer as the shield electrode **116**, the second gate electrode **250** (second scanning signal line **107**) overlaps the first oxide semiconductor layer **180a** through the second insulating layer **212**. The capacitive element **140r** is formed by a transparent conductive film and the second metal oxide conductive layer **176b** forming the second gate electrode **151** that overlaps across the second insulating layer **212**. The second metal oxide conductive layer **176b** has a structure connected to the shield electrode **116** by the fifth contact hole **166**. The EL element **142r** has a structure in which the electron transport layer **222**, the electron injection layer **224**, the light emitting layer **226**, an electron blocking layer **227**, the hole transport layer **228**, the hole injection layer **230**, and the second electrode **232** are stacked from the first electrode **220** (cathode) side. The planarization layer **246** and the passivation layer **248** are disposed on top of the light emission control transistor **137r** and other elements. The EL element **142r** is disposed above the planarization layer **246**.

[0305] FIG. **50** shows the planar layout of the EL element **142** and the cross-sectional structures of the lines E1-E2 and E3-E4. A peripheral edge of the first electrode **220** is covered by a separation wall **262**. The eighth contact hole **264** where the first electrode **220** is connected to the light emission control transistor **137** is also disposed at a position covered by the separation wall **262**. When the electron transport layer **222** is formed of a coated material, the electron transport layer **222** is disposed on the top surface of the first electrode **220** in the region surrounded by the separation wall **262**. When the electron injection layer **224**, the electron blocking layer **227**, the hole transport layer **228**, and the hole injection layer **230** are formed by vapor deposition, they are disposed to cover the separation wall **262** and extend over the entire display part **102**. The light emitting layer **226** is disposed so that it overlaps the opening of the separation wall **262**, using a shadow mask during evaporation. The light emitting layer **226** can also be formed using an inkjet printing method, gravure offset printing method, or other methods.

[0306] As is apparent from FIG. **48** and FIG. **50**, the EL element **142**, the first transistor **138**, the second transistor **139**, the drive transistor **136**, and the emission control transistor **137** are disposed in an overlaid arrangement. The gate electrodes, source and drain electrodes, and oxide semiconductor layers of these transistors forming the pixel circuit are formed of transparent materials that transmit visible light, so that light can be emitted outside through the transparent resin substrate **200** even if the EL element **142** is a bottom emission type.

Eighth Embodiment

[0307] The drive transistor **136** that drives the EL element **142** has the capacitive element **140** to hold the voltage based on the data signal. The voltage held in the capacitive element **140** fluctuates by ΔV_{gd} when the selective transistor **138** is turned off due to the parasitic capacitance C_{gd} between the gate and drain of the selective transistor **138**. This is not a problem when the capacitance of the capacitance element **140** is large, but when the pixel size is smaller due to higher resolution in small and medium-sized displays and the capacitance element **140** cannot be made larger, this effect cannot be neglected. Also, in the current write method, it is necessary to increase

the write time when the capacitance of the capacitive element **140** is increased, but the number of pixels and drive frequency do not allow for sufficient write time, which causes a problem with gradation expression.

[0308] FIG. **51** shows an example of a pixel circuit that can suppress the above-mentioned ΔV_{gd} fluctuation. Specifically, the sub-pixel **105** has a configuration in which the first transistor **138** (select transistor) is connected to the gate of the drive transistor **136** to apply the data signal, and the light emission control transistor **137** is connected between the EL element **142** and the drive transistor **136**, the second transistor **139** is connected between the data line signal **108** and the drain of the light emission control transistor **137**, and the second capacitive element **274** is connected between the second transistor **139** and the second gate electrode of the drive transistor **136**, thereby, to ensure that the voltage of the capacitive element **140** does not fluctuate by ΔV_{gd} when the gate voltage of the first transistor **138** turns down.

[0309] FIG. **52** shows a planar layout of the sub-pixel **105** shown in FIG. **51**, and FIG. **53** shows a partial cross-sectional structure of the sub-pixel **105**, showing the first transistor **138**, the second capacitance element **274**, and the EL element **142**. The second capacitive element **274** has a structure in which a second capacitance electrode **272** and the fourth metal oxide conductive layer **176d** extending from the first transistor **138** overlap across the second insulating layer **212**. The second capacitance electrode **272** can be formed with the same layer as the second gate electrode **151** of the drive transistor **136**, so that it is not necessary to add a new layer and can be formed without increasing the number of photomasks.

[0310] As shown in the layout diagram of sub-pixel **105** in FIG. **54** and the partial cross-sectional view of sub-pixel **105** in FIG. **55**, the second capacitive element **274** may be formed by disposing the second gate electrode **151** of the drive transistor **136** connected to the drain of the light emission control transistor **137** and the fourth metal oxide conductive layer **176d** extending from the first transistor **138**, with the second insulating layer **212** in between.

[0311] As described above, by providing the second capacitive element **274**, it is possible to suppress the voltage fluctuation of the capacitive element **140** due to the gate voltage fluctuating by ΔV_{gd} when the selective transistor **138** is turned off due to the gate-drain capacitance C_{gd} . This embodiment can be implemented in combination with the display device with touch and fingerprint sensors shown in the first embodiment as appropriate.

Ninth Embodiment

[0312] This embodiment shows an example of a light-extraction structure of the EL element **142** disposed in the display device with the touch and fingerprint sensor **100**.

[0313] FIG. **56** shows a cross-sectional structure of the sub-pixel **105** in the present embodiment. The sub-pixel **105** according to the present embodiment has a structure in which a wire-grid polarizer **250** is disposed on the side where the EL element **142** emits light. For example, the wire-grid polarizer **250** is disposed between the transparent resin substrate **200** with first sensor electrode **112** and second sensor electrode **114** and the EL element **142**. FIG. **56** shows a cross-sectional structure of the sub-pixel **105** in the present embodiment. The sub-pixel **105** according to the present embodiment has a structure in which a wire-grid polarizer **250** is disposed on the side where the EL element **142** emits light. For example, the wire-grid polarizer **250** is disposed between the transparent resin substrate **200** with first sensor electrode **112** and second sensor electrode **114** and the EL element **142**.

[0314] Since the EL element **142** emits light to the side of the transparent resin substrate **200**, the first electrode **220** is formed by a transparent conductive film and the second electrode **232** is formed by a metal film. The EL element **142** shown in the present embodiment further has a structure in which a light scattering layer **251** is disposed between the electron injection layer **230** and the second electrode **232**. The light scattering layer **251** is formed by applying a transparent adhesive ink **254** containing transparent light scattering beads **252** onto the electron injection layer **230**. For example, the transparent adhesive ink **254** including transparent light scattering beads **252**

can be applied to the area of the sub-pixel **105** by a printing method such as ink jet printing to form the light scattering layer **251**.

[0315] FIG. **58** shows the detailed construction of the wire-grid polarizer **250**. The wire-grid polarizer **250** has a structure in which the fine wire patterns are periodically arranged. The fine wire pattern is formed of fine metal wires **258** formed of aluminum (Al), aluminum-silver alloy (AlAg), silicon or a neodymium added aluminum alloy (Al—Si, Al—Nd), and the like. A light-absorbing layer **256** that absorbs visible light may be disposed on the shield electrode **116** side of the fine metal wires **258**. The light absorbing layer **256** is preferably formed of a semiconductor material having a visible light absorbing band such as silicon (Si), germanium (Ge), silicon germanium (SiGe), or a high melting point metal such as chromium (Cr), cobalt (Co), nickel (Ni), tantalum (Ta), molybdenum (Mo), titanium (Ti), and niobium (Nb) and silicon. The fine metal wires **258** have a width of 100 nm or less, preferably 70 nm or less, a thickness of 100 nm or more, preferably 200 nm or more, and are arranged at a pitch of less than half the wavelength of visible light, (for example, 200 nm or less). Accordingly, although the glossy surface of the metal is visually visible, the light absorbing layer **256** is disposed over the metal thin line **258** on the viewing surface of the wire-grid polarizer **250**, thereby preventing the display screen from being mirrored.

[0316] FIG. **59** shows an example of a wire-grid polarizer **250** on an insulating layer **260**. The fine metal wires **258** constituting the wire-grid polarizer **250** can also serve as the shield electrode **116** because it is disposed at a pitch of less than half the wavelength of visible light (for example, 200 nm or less). At this case, it is preferred that the fine metal wires **258** be controlled at a constant potential (for example, a grounding potential) as well as the shield electrode **116**.

[0317] The wire-grid polarizer **250** is a linear polarizer and has a transmission polarization axis and a reflection polarization axis. As shown in FIG. **68**, it is possible to transmit the polarization component (TM wave) parallel to the transmission polarization axis of the light emitted from the EL element **142** to be emitted from the transparent resin substrate **200** and to reflect the polarization component (TE wave) parallel to the reflection polarization axis by providing the wire-grid polarizer **250**. That is, half of the light emitted from the EL element **142** is reflected at the wire-grid polarizer **250** and again incident on the EL element **142**. The light re-incident on the EL element **142** is scattered by the light scattering layer **251** so that the polarization axis is random. It is then emitted again from the EL element **142**, some of which is transmitted through the wire-grid polarizer **250** and exits outward, and the rest of which is reflected. It is possible to provide the wire-grid polarizer **250** and the light scattering layer **251** so that the light emitted from the EL element **142** is reflected multiple times and the polarization axis of the emitted light converges in a single direction.

[0318] Although not shown in FIG. **56**, the display device with the touch and fingerprint sensor **100** is disposed with a polarizing axis rotator on the display screen side for enhanced contrast. The polarization rotator combines a $\frac{1}{2}$ phase difference plate with a straight polarization plate and a $\frac{1}{2}$ phase difference delay axis is inclined by 45 degrees. In this case, the linear polarization axis of the polarization rotator of the polarization axis is inclined at 45 degrees relative to the transmission polarization axis of the wire-grid polarizer **250**, as shown in FIG. **60**, thereby greatly improving the extraction efficiency of the light emitted from the EL element **142**.

[0319] The direction of the transmission polarization axis of the wire-grid polarizer **250** can be freely set by changing the direction in which the metal wires **258** extend. FIG. **61** shows an example in which patterns of the fine metal wires **258** are disposed in areas surrounded by the scanning signal line **106** and the data signal line **108** (areas of sub-pixel **105**). As shown in FIG. **61**, the fine metal wires **258** have a pattern that extends in a direction parallel to the direction in which the scanning signal line **106** extends, so that the transmission polarization axis is arranged in a direction parallel to the direction in which the data signal line **108** extends. Note that although not shown in the figure, the fine metal wires **258** may have patterns extending in a direction parallel to the direction in which the data signal line **108** extends. FIG. **62** shows an example where the

pattern of the fine metal wires **258** is disposed at a predetermined angle to the scanning signal lines **106** and the data signal lines **108**, so that the transmitted polarization axis is disposed in a direction perpendicular to the longitudinal direction of the fine metal wires **258**.

[0320] FIG. **57** shows an example of a wire-grid polarizer **250** embedded in a planarization layer **246**. The fine metal wires **258** are formed with a thickness of about 100 nm to 200 nm. It is possible to arrange the wire-grid polarizer **250** in the form of a so-called in-cell structure and still provide the EL element **142** without interfering with the planarity, by arranging the metallic wires **258** so that they are embedded in the planarization layer **246**.

[0321] FIG. **66** shows an example of the wire-grid polarizer **250** on the top surface of the first electrode **220**. The fine metal wires **258** and the light-absorbing layer **256** included in the wire-grid polarizer **250** are formed on top of the transparent conductive layer forming the first electrode **220**. The fine metal wires **258** and the light absorbing layer **256** form an uneven structure on the top surface of the first electrode **220**, but the electron transport layer **222** is disposed with a coated material to embed the fine metal wires **258** so that it does not affect the light emitting layer **226** and prevents a short circuit with the second electrode **232**.

[0322] FIG. **67** shows a plan view of the first electrode **220** and the metal fine wires **258**. The fine metal wires **258** are disposed on top of the transparent conductive film that forms the first electrode **220**. The fine metal wires **258** is formed to extend from the side of one end of the first electrode **220** to the side of the other end. As shown in FIG. **67**, a metal pattern surrounding the periphery of the first electrode **238** is disposed with the metal film forming the metallic thin wire **258**, and the transparent conductive film (first electrode **220**) can be made less resistant by connecting the fine metal wires **258**.

[0323] As shown in this embodiment, the wire-grid polarizer **250** is disposed in the layer forming the display device with the touch and fingerprint sensor **100**, so that even if the polarization axis rotating plate is disposed to improve contrast, the light extraction efficiency can be greatly improved.

Tenth Embodiment

[0324] This embodiment shows further aspects of the sealing structure and drawer wiring structure shown in the first embodiment.

[0325] FIG. **63A** shows a configuration in which the second sensor electrode **114** is connected to some wiring or circuit on the transparent resin substrate **200** by the drawer wiring **147** formed of the same layer as the data signal line **108**. The drawer wiring **147** is disposed on the first insulating layer **210** and has a structure connected to the contact hole **159** through the first insulating layer **210**, the fourth transparent resin layer **202d**, and the third transparent resin layer **202c**. The second insulating layer **212** is disposed on the first drawer wiring **147** and the first contact hole **159** and is further covered with a silicon nitride film **214c** to prevent moisture from entering from the outside.

[0326] FIG. **63B** shows a configuration in which the second sensor electrode **114** is connected to a wiring or circuit on the transparent resin substrate **200** by the drawer wiring **147** formed of the same layer as the scanning signal line **106** or the second scanning signal line **107**. The drawer wiring **147** is disposed on the second insulating layer **212** and is connected to the first drawer wiring **147a** formed on the third transparent resin layer **202c** in the same layer as the shield electrode **116** by the contact hole **159** passing through the second insulating layer **212**, the first insulating layer **210**, and the fourth transparent resin layer **202d**. Further, the first drawer wiring **147a** is connected to the second sensor electrode **114** by the contact hole **169** formed in the third transparent resin layer **202c**. Such structures also allow the second sensor electrode **114** to connect to wirings or circuitry on the transparent resin substrate **200**.

[0327] FIG. **64A** shows a configuration in which the drawer wiring **147** is disposed on the second insulating layer **212** with respect to the structure shown in FIG. **22A**. The drawer wiring **147** is formed of the same layer as the second scanning signal line **107**. The overlying of the drawer wiring **147** with the silicon nitride film **214c** allows the drawer wiring **147** to form a structure that

is in intimate contact with the sealing layer **236**, even though the drawer wiring **147** has an outwardly extending structure to form the second connecting terminal **146b**, thereby increasing reliability.

[0328] FIG. **64B** shows a connection structure between the second electrode **232** and the third connecting terminal **146c**. The second electrode **232** is drawn out to the end of the transparent resin substrate **200** and connected to the drawer wiring **147** formed in the same layer as the second scanning signal line **107**. The drawer wiring **147** has a structure that extends outward to form the third connecting terminal **146c**, but even in this structure, the drawer wiring **147** is covered with the silicon nitride film **214c**, so that a structure that adheres closely to the sealing layer **236** can be formed and reliability can be enhanced.

[0329] FIG. **65A** shows a connecting structure of the data signal line **108** and the first connecting terminal **146a**. The data signal line **108** is drawn to the end of the transparent resin substrate **200** and connected to the drawer wiring **147** formed of the same layer as the second scanning signal line **107**. Although the drawer wiring **147** has an outer extending structure to form the first connecting terminal **146a**, the drawer wiring **147** can also be covered with the silicon nitride film **214c** to form a structure that is in close contact with the sealing layer **236**, thereby enhancing reliability.

[0330] FIG. **65B** shows a configuration in which the drawer wiring **147** is directly connected to the second sensor electrode **114** by a contact hole **159** passing through the second insulating layer **212**, the first insulating layer **210**, the fourth transparent resin layer **202d**, and the third transparent resin layer **202c** with respect to FIG. **63B**. Such an arrangement also allows the second sensor electrode **114** to connect to wirings or circuitry on the transparent resin substrate **200**.

[0331] In the structures shown in FIG. **16A**, FIG. **16B**, FIG. **19A**, FIG. **19B**, FIG. **21A**, FIG. **21B**, FIG. **49**, FIG. **53**, and FIG. **55**, when external light enters the display panel from the outside, it is reflected by the various metals that make the display panel and is emitted again to the outside, which may cause a significant decrease in contrast. To prevent such a reduction in contrast, a circular polarizer (an optical member combining a linear polarizer and a quarter-wave plate) is actually installed in close contact with the transparent resin layer **202a**, but is not shown in the drawings above.

[0332] FIG. **56**, FIG. **57**, and FIG. **66** show display panels with built-in wire-grid polarizers **250** to improve light extraction efficiency, but when external light enters the panel, it is reflected by the various electrodes and wiring formed by the metal materials that make up the display panel and is emitted again to the outside world, resulting in a significant drop in contrast. To prevent such a reduction in contrast, it is preferable to provide a light-absorbing layer similar to the light-absorbing layer **256** that constitutes the wire-grid polarizer **250** on the lower layer of the electrodes and wiring formed by the metallic materials that constitute the display panel, but this layer is omitted in the above drawing.

Claims

1. A display device with touch sensor, comprising: a transparent resin substrate comprising a first transparent resin layer, a second transparent resin layer, a third transparent resin layer, and a fourth transparent resin layer laminated in this order; a plurality of first sensor electrodes disposed between the first transparent resin layer and the second transparent resin layer and extending in a first direction; a plurality of second sensor electrodes disposed between the second transparent resin layer and the third transparent resin layer and extending in a second direction intersecting the first direction; a shield electrode disposed between the third transparent resin layer and the fourth transparent resin layer, the shield electrode including a first opening; a first insulating layer on the fourth transparent resin layer; a second insulating layer on the first insulating layer; a third insulating layer on the second insulating layer; a sealing layer covering the third insulating layer; a plurality of connecting terminals between the first insulating layer and the second insulating layer;

and a drive circuit connected to the plurality of connecting terminals, wherein the plurality of first sensor electrodes and the plurality of connecting terminals are connected through a first contact hole passing through the first insulating layer, the fourth transparent resin layer, the third transparent resin layer, and the second transparent resin layer, the first contact hole is disposed inside the first opening and covered with the third insulating layer and the sealing layer, the plurality of connecting terminals is disposed in a region exposed from the third insulating layer and the sealing layer, and the shield electrode is extended in a region overlapping the drive circuit.

2. The display device with touch sensor according to claim 1, further comprising a plurality of drawer wirings between the first insulating layer and the second insulating layer, wherein the plurality of second sensor electrodes and the plurality of drawer wirings are connected through second contact holes passing through the first insulating layer, the fourth transparent resin layer, and the third transparent resin layer, and the second contact holes are disposed outside the shield electrode and covered with the third insulating layer and the sealing layer.

3. The display device with touch sensor according to claim 1, wherein the transparent resin substrate has corners, and the corners have a round shape.

4. The display device with touch sensor according to claim 1, wherein the drive circuit includes a scanning signal line drive circuit block, a data signal line drive circuit block, and a touch and fingerprint sensor detection circuit block.

5. The display device with touch sensor according to claim 1, further comprising a display part disposed with a plurality of pixels, the display part includes a first electrode disposed for each of the plurality of pixels, a second electrode extending over the plurality of pixels, and a light emitting layer between the first electrode and the second electrode, wherein the second electrode extends over the third insulating layer and is covered with the sealing layer.

6. The display device with touch sensor according to claim 5, further comprising: a plurality of data signal lines disposed on the display part and extending in the first direction; and a plurality of switching circuits between the display part and the plurality of connecting terminals, wherein each of the plurality of switching circuits switches the connection between one connecting terminal selected from the plurality of connecting terminals and two or more data signal lines of the plurality of data signal lines, the plurality of switching circuits and the plurality of connecting terminals are disposed along the second direction, the first contact hole is disposed between the plurality of connecting terminals and the plurality of switching circuits, and each of the plurality of first sensor electrodes are placed between the plurality of switching circuits and extend to the first contact hole.

7. The display device with touch sensor according to claim 6, wherein the plurality of switching circuits is disposed in each of two sets along the second direction, and each of the plurality of first sensor electrodes is placed between each of the two sets of the plurality of switching circuits.

8. The display device with touch sensor according to claim 5, wherein each of the plurality of pixels includes a transistor connected to the first electrode and a capacitive element, and the transistor and the capacitive element are configured to include an oxide semiconductor layer and a transparent conductive layer.

9. The display device with touch sensor according to claim 8, further comprising: a wire-grid polarizer disposed between the first electrode and the transparent resin substrate; and a light scattering layer disposed between the light emitting layer and the second electrode.

10. The display device with touch sensor according to claim 9, wherein the shield electrode is interposed between the transistor and the plurality of second sensor electrodes, and the wire-grid polarizer is disposed on a surface of the shield electrode.

11. The display device with touch sensor according to claim 9, wherein the wire-grid polarizer is disposed between the transistor and the first electrode.

12. The display device with touch sensor according to claim 9, wherein the wire-grid polarizer includes a light-absorbing layer on the transparent resin substrate and a fine metal wire on the first electrode.

13. The display device with touch sensor according to claim 1, further comprising: a display part including a plurality of pixels, a plurality of scanning signal lines extending in the second direction, and a plurality of data signal lines extending in the first direction; a peripheral area outside the display part; a scanning signal line drive circuit for outputting a scanning signal to the plurality of scanning signal lines; and a scan circuit for outputting a scan signal to the second sensor electrode, wherein the scanning signal line drive circuit and the scan circuit are disposed on both sides of the display part in the peripheral area, and extend in the first direction, the scanning signal line drive circuit is disposed close to the display part, and the scan circuit is disposed outside the scanning signal line drive circuit.
