

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12405670
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Haga; Hiroshi et al.

Tactile presentation device and control method

Abstract

A tactile presentation device comprising: a contact face; a plurality of electrodes arranged along the contact face; a first control unit controlling operations of the electrodes for detecting contact or approach of an object toward the 5 contact face; a second control unit controlling operations of the electrodes for presenting a tactile sense to the contact face; and a third control unit causing a part of the plurality of the electrodes to be controlled by the first control unit, sequentially changing the electrode to be controlled by 10 the first control unit to another electrode among the plurality of the electrodes, and causing electrodes other than the electrode that is controlled by the first control unit to be controlled by the second control unit.

Inventors:	Haga; Hiroshi (Kanagawa, JP), Sugimoto; Daisuke (Kanagawa, JP)
Applicant:	TIANMA MICROELECTRONICS CO., LTD. (Shenzhen, CN)
Family ID:	61971476
Assignee:	TIANMA MICROELECTRONICS CO., LTD. (Shenzhen, CN)
Appl. No.:	18/486285
Filed:	October 13, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240045507 A1	Feb. 08, 2024

Foreign Application Priority Data

JP	2016-207062	Oct. 21, 2016
JP	2017-155769	Aug. 10, 2017

Related U.S. Application Data

division parent-doc US 17661968 20220504 US 11822725 child-doc US 18486285
division parent-doc US 17247816 20201223 US 11353961 20220607 child-doc US 17661968
division parent-doc US 15789122 20171020 US 10908688 20210202 child-doc US 17247816

Publication Classification

Int. Cl.: **G06F3/01** (20060101); **G06F3/041** (20060101); **G06F3/044** (20060101)

U.S. Cl.:

CPC **G06F3/016** (20130101); **G06F3/0416** (20130101); **G06F3/04166** (20190501);
G06F3/044 (20130101); **G06F3/0446** (20190501);

Field of Classification Search

CPC: G06F (3/016); G06F (3/0416); G06F (3/04166); G06F (3/044); G06F (3/0446); G06F (3/0412); G06F (3/04164); G06F (3/04847); G06F (3/0488)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5565658	12/1995	Gerpheide et al.	N/A	N/A
9477356	12/2015	Shen	N/A	G06F 3/0443
2011/0285666	12/2010	Poupyrev et al.	N/A	N/A
2011/0285667	12/2010	Poupyrev et al.	N/A	N/A
2012/0062516	12/2011	Chen et al.	N/A	N/A
2013/0307789	12/2012	Karamath et al.	N/A	N/A
2014/0025848	12/2013	Bisgrove et al.	N/A	N/A
2014/0071088	12/2013	Hong et al.	N/A	N/A
2014/0146005	12/2013	Hong et al.	N/A	N/A
2014/0176486	12/2013	Lee et al.	N/A	N/A
2015/0103024	12/2014	Haga et al.	N/A	N/A
2015/0130770	12/2014	Takatori	N/A	N/A
2016/0357342	12/2015	Olley et al.	N/A	N/A
2017/0147141	12/2016	Khazeni	N/A	G06F 3/041662

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
H11505641	12/1998	JP	N/A
2011002926	12/2010	JP	N/A
2011248884	12/2010	JP	N/A
2012529091	12/2011	JP	N/A
2014106733	12/2013	JP	N/A
2014106743	12/2013	JP	N/A
2015111391	12/2014	JP	N/A
2014002405	12/2013	WO	N/A

OTHER PUBLICATIONS

Primary Examiner: Sarma; Abhishek

Attorney, Agent or Firm: NIXON & VANDERHYE

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION (1) This application is a Divisional of application Ser. No. 17/661,968, filed on May 4, 2022, which is a divisional of U.S. patent application Ser. No. 17/247,816 filed on Dec. 23, 2020, which is a divisional of U.S. patent application Ser. No. 15/789,122 filed on Oct. 20, 2017, which claims priority under 35 U.S.C. § 119(a) on Patent Application No. 2016-207062 filed in Japan on Oct. 21, 2016 and Patent Application No. 2017-155769 filed in Japan on Aug. 10, 2017, the entire contents of which are hereby incorporated by reference.

BACKGROUND OF THE INVENTION

Field of the Invention

(1) The present invention relates to a tactile presentation device and a control method for controlling a tactile presentation device presenting a tactile sense on a contact face together with detecting contact on the contact face.

Description of the Related Art

(2) Technologies for presenting a tactile sense to a surface of a touch panel using an electrostatic force have been developed. The presentation of a tactile sense represents causing a texture sense that can be perceived as a tactile sense when a user is brought into contact with the surface of an object with which the user can be brought into contact. For example, in a case where a tactile sense is presented to a specific position on the surface of a touch panel, a user brought into contact with the surface of the touch panel can notice the specific position on the surface using a tactile sense. In PCT International Publication No. 2014/002405 and U.S. Patent Application Publication No. 2013/0307789, tactile presentation devices each presenting a tactile sense to the surface of a touch panel are disclosed.

(3) A tactile presentation device including a touch panel needs to have both a function for detecting a contact position on the surface of the touch panel and a function for presenting a tactile sense to the surface of the touch panel. In the tactile presentation device disclosed in PCT International Publication No. 2014/002405, a plurality of electrodes are arranged on in a planar shape, and voltages used for detecting a contact position are supplied to the plurality of electrode in a certain period, and voltages used for presenting a tactile sense are supplied to the plurality of electrodes in the other period.

(4) Accordingly, the tactile presentation device operates for detecting a contact position during the certain period and operates to present a tactile sense during the other period. The function for detecting a contact position on the surface of the touch panel and the function for presenting a tactile sense to the surface of the touch panel are realized alternately in time.

SUMMARY OF THE INVENTION

(5) In the tactile presentation device disclosed in PCT International Publication No. 2014/002405, in the period in which the tactile presentation device operates to detect a contact position on the surface of the touch panel, a tactile sense cannot be presented to the surface of the touch panel. For this reason, there is a problem in that a tactile sense felt by a user during the use of the tactile

presentation device is interrupted.

(6) A tactile presentation device according to an aspect of the present disclosure, comprising: a contact face; a plurality of electrodes arranged along the contact face; a first control unit controlling operations of the electrodes for detecting contact or approach of an object toward the contact face; a second control unit controlling operations of the electrodes for presenting a tactile sense to the contact face; and a third control unit causing a part of the plurality of the electrodes to be controlled by the first control unit, sequentially changing the electrode to be controlled by the first control unit to another electrode among the plurality of the electrodes, and causing electrodes other than the electrode that is controlled by the first control unit to be controlled by the second control unit.

(7) In a tactile presentation device according to the present disclosure, a plurality of electrodes are arranged along a contact face. Some electrodes are used for detecting contact or approach of an object toward the contact face, and the other electrodes are used for presenting a tactile sense to the contact face. The electrodes used for detecting contact or approach of an object toward the contact face are sequentially changed. Each of the electrodes are used for detecting contact or approach of an object at a specific timing and is used for presenting a tactile sense at the other timings.

(8) The above and further objects and features will more fully be apparent from the following detailed description with accompanying drawings.

(9) It is to be understood that both the foregoing general description and the following detailed description are exemplary and explanatory and are not restrictive of this disclosure.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a schematic perspective view that illustrates an example of the outer appearance of a tactile presentation device;

(2) FIG. 2 is a block diagram that illustrates an example of the internal functional configurations of the tactile presentation device;

(3) FIG. 3 is a block diagram that illustrates the internal configurations of a tactile panel and a tactile panel driving unit according to Embodiment 1;

(4) FIG. 4 is a schematic circuit diagram that illustrates the internal configuration of an X electrode driving circuit according to Embodiment 1;

(5) FIG. 5 is a schematic circuit diagram that illustrates the internal configuration of a Y electrode driving circuit according to Embodiment 1;

(6) FIG. 6 is a schematic circuit diagram that illustrates the internal configuration of a touch panel driving circuit according to Embodiment 1;

(7) FIG. 7 is a timing diagram that illustrates an example of the operation of each electrode according to Embodiment 1;

(8) FIG. 8 is a timing diagram that illustrates another example of the operation of each electrode according to Embodiment 1;

(9) FIG. 9 is a schematic plan view that illustrates a model of a tactile panel for description;

(10) FIGS. 10A to 10D are schematic views that illustrate a positional relation between an X electrode and a contact portion where a user's finger touches a contact face;

(11) FIG. 11 is a schematic view that illustrates a relation between time and the positions of a contact portion and an X electrode;

(12) FIG. 12 is a characteristic diagram that illustrates a change in an electrostatic force generated at a finger;

(13) FIG. 13 is a schematic view that illustrates a relation between time and the positions of a contact portion and an X electrode in a case where the position of the X electrode controlled for detecting contact is discretely changed in the model of the tactile panel illustrated in FIG. 9;

- (14) FIG. **14** is a schematic circuit diagram that illustrates the internal configuration of a touch panel driving circuit according to Embodiment 2;
- (15) FIG. **15** is a block diagram that illustrates the internal configurations of a tactile panel and a tactile panel driving unit according to Embodiment 3;
- (16) FIG. **16** is a schematic circuit diagram that illustrates the internal configuration of an electrode driving circuit according to Embodiment 3;
- (17) FIG. **17** is a schematic circuit diagram that illustrates the internal configuration of a touch panel driving circuit according to Embodiment 3;
- (18) FIG. **18** is a timing diagram that illustrates an example of a change in the state of each electrode with respect to time according to Embodiment 3;
- (19) FIG. **19** is a schematic circuit diagram that illustrates the internal configurations of a touch panel driving circuit and a switching unit according to Embodiment 4;
- (20) FIG. **20** is a schematic view that illustrates an example of a tactile panel according to Embodiment 4;
- (21) FIG. **21** is a timing diagram that illustrates an example of the operation of each electrode according to Embodiment 4;
- (22) FIGS. **22A** to **22C** are schematic views that illustrate the states of the tactile panel at specific timings according to Embodiment 4;
- (23) FIG. **23** is a block diagram that illustrates the internal configuration of a tactile panel according to Embodiment 5;
- (24) FIG. **24** is a block diagram that illustrates the internal configurations of a tactile panel and a tactile panel driving unit according to Embodiment 6;
- (25) FIG. **25** is a schematic circuit diagram that illustrates the internal configuration of a touch panel driving circuit according to Embodiment 6;
- (26) FIG. **26** is a schematic circuit diagram that illustrates the internal configuration of an X electrode driving circuit according to Embodiment 6;
- (27) FIGS. **27A** to **27D** are graphs that schematically illustrate the waveforms of voltages acquired by an X electrode driving circuit according to Embodiment 6;
- (28) FIG. **28** is a schematic circuit diagram that illustrates the internal configuration of a Y electrode driving circuit according to Embodiment 6;
- (29) FIGS. **29A** to **29D** are graphs that schematically illustrate the waveforms of voltages acquired by a Y electrode driving circuit according to Embodiment 6;
- (30) FIG. **30** is a circuit diagram acquired by modeling a state in which an X electrode X.sub.1 is connected to an AC voltage source through a current detecting unit, and a voltage generated by the AC voltage source is superimposed in all the other electrodes;
- (31) FIG. **31** is a circuit diagram that models the states of the electrodes according to Embodiment 2; and
- (32) FIG. **32** is a circuit diagram that illustrates an example of the configuration of voltage superimposing units according to Embodiment 6.

DESCRIPTION OF THE PREFERRED EMBODIMENTS

(33) Hereinafter, embodiments of the present disclosure will be described more specifically with reference to the drawings.

Embodiment 1

(34) FIG. **1** is a schematic perspective view that illustrates an example of the outer appearance of a tactile presentation device. The tactile presentation device is a computer such as a smartphone or a tablet computer. The tactile presentation device includes a planar contact face **11** for contact using a user's finger. On the contact face **11**, an image is displayed, and, when a user's finger is brought into contact with the contact face **11**, a tactile sense is presented, and a contact position on the contact face **11** is detected.

(35) FIG. **2** is a block diagram that illustrates an example of the internal functional configurations

of a tactile presentation device. The tactile presentation device includes: an arithmetic operation unit **31** that performs an arithmetic operation; a random access memory (RAM) **32** that stores temporary data; a storage unit **33** that has non-volatility; and an input/output unit **34** performing input/output of data.

(36) The storage unit **33** is, for example, a hard disk or a nonvolatile semiconductor memory. The input/output unit **34**, for example, is a communication unit that performs wired or wireless communication with an external device of the tactile presentation device. In addition, the tactile presentation device includes a display panel **36** such as a liquid crystal display panel or an electroluminescence (EL) display panel that displays an image. A display panel driving unit **35** driving the display panel **36** to display an image is connected to the display panel **36**. The display panel driving unit **35** is connected to the arithmetic operation unit **31**. The display panel driving unit **35** receives an input of image data from the arithmetic operation unit **31** and displays an image on the display panel **36** based on the image data.

(37) In addition, the tactile presentation device includes a tactile panel **1** used for detecting a contact position on the contact face **11** together with presenting a tactile sense. The tactile panel **1** overlaps with the display panel **36**. A tactile panel driving unit **2** that drives the tactile panel **1** is connected to the tactile panel **1**. The tactile panel driving unit **2** is connected to the arithmetic operation unit **31**.

(38) FIG. **3** is a block diagram that illustrates the internal configurations of a tactile panel **1** and a tactile panel driving unit **2** according to Embodiment 1. The tactile panel **1** includes a transparent substrate **12** such as a glass substrate. On the substrate **12**, a plurality of linear X electrodes (first linear electrodes) **13** are arranged in parallel. In FIG. **3**, the X electrodes **13** are denoted using broken lines. In addition, on the substrate **12**, a plurality of linear Y electrodes (second linear electrodes) **14** are arranged in parallel. The plurality of X electrodes **13** and the plurality of Y electrodes **14** are insulated from each other. In addition, the plurality of X electrodes **13** and the plurality of Y electrodes **14** intersect each other. Here, a direction along the linear X electrodes **13** will be set as an X direction, and a direction along the linear Y electrodes **14** will be set as a Y direction. A cover layer **15** having an insulating property is superimposed on the substrate **12** with the X electrodes **13** and the Y electrodes **14** interposed therebetween. The surface of the cover layer **15** is the contact face **11**.

(39) The tactile panel driving unit **2** includes a touch panel driving circuit (first control unit) **22** for controlling the operations of the X electrodes **13** and the Y electrodes **14** used for detecting contact of an object on the contact face **11**. The touch panel driving circuit **22** is a circuit that is used for realizing the function of a touch panel detecting contact of an object on the contact face **11** by using the X electrodes **13** and the Y electrodes **14**. The tactile panel driving unit **2** includes an X electrode driving circuit **23** used for controlling the operations of the X electrodes **13** for presenting a tactile sense on the contact face **11** and a Y electrode driving circuit **24** used for controlling the operations of the Y electrodes **14** for presenting a tactile sense on the contact face **11**. The X electrode driving circuit **23** and the Y electrode driving circuit **24** are circuits used for presenting a tactile sense on the contact face **11** by using the X electrodes **13** and the Y electrodes **14** and correspond to a second control unit. The tactile panel driving unit **2** includes a first switching unit **25** that is connected to the plurality of the X electrodes **13** and a second switching unit **26** that is connected to the plurality of the Y electrodes **14**. The first switching unit **25** is configured to connect some X electrodes **13** to the touch panel driving circuit **22** and connect the other X electrodes **13** to the X electrode driving circuit **23** and to be able to switch the connection of each X electrode **13** to one side to the other side. The second switching unit **26** is configured to connect some Y electrodes **14** to the touch panel driving circuit **22** and connect the other Y electrodes **14** to the Y electrode driving circuit **24** and to be able to switch the connection of each Y electrode **14** to one side to the other side.

(40) Furthermore, the tactile panel driving unit **2** includes a control circuit **21**. The control circuit **21** is connected to the touch panel driving circuit **22**, the X electrode driving circuit **23**, the Y

electrode driving circuit **24**, the first switching unit **25**, and the second switching unit **26**. In addition, the control circuit **21** is connected to the arithmetic operation unit **31**. The control circuit **21** receives an input of a control signal from the arithmetic operation unit **31** and controls the operations of the touch panel driving circuit **22**, the X electrode driving circuit **23**, the Y electrode driving circuit **24**, the first switching unit **25**, and the second switching unit **26**. The control circuit **21**, the first switching unit **25**, and the second switching unit **26** correspond to a third control unit.

(41) FIG. **4** is a schematic circuit diagram that illustrates the internal configuration of the X electrode driving circuit **23** according to Embodiment 1. The X electrode driving circuit **23** includes a plurality of single-pole double-throw switches **231** and a first AC voltage source **232** that generates an AC voltage having a predetermined first frequency f_1 . The internal circuit of the X electrode driving circuit **23** is configured to connect each X electrode **13** connected through the first switching unit **25** to one of the first AC voltage source **232** and the ground by using each single-pole double-throw switch **231**. Each single-pole double-throw switch **231** is controlled by the control circuit **21** and performs switching of a connection between each X electrode **13** and the first AC voltage source **232** or the ground. The internal circuit of the X electrode driving circuit **23** illustrated in FIG. **4** corresponds to a first signal applying circuit.

(42) FIG. **5** is a schematic circuit diagram that illustrates the internal configuration of the Y electrode driving circuit **24** according to Embodiment 1. The Y electrode driving circuit **24** includes a plurality of single-pole double-throw switches **241** and a second AC voltage source **242** that generates an AC voltage having a predetermined second frequency f_2 . The internal circuit of the Y electrode driving circuit **24** is configured to connect each Y electrode **14** connected through the second switching unit **26** to one of the second AC voltage source **242** and the ground by using each single-pole double-throw switch **241**. Each single-pole double-throw switch **241** is controlled by the control circuit **21** and performs switching of a connection between each Y electrode **14** and the second AC voltage source **242** or the ground. The internal circuit of the Y electrode driving circuit **24** illustrated in FIG. **5** corresponds to a second signal applying circuit.

(43) The tactile presentation device presents a tactile sense to the contact face **11** by using the operations of the X electrode driving circuit **23** and the Y electrode driving circuit **24**. In a case where a user brings his finger into contact with the contact face **11**, this finger is equivalent to an electrode that faces the X electrode **13** or the Y electrode **14** with an insulating body interposed therebetween and is connected to the ground through predetermined impedance. In a case where a voltage is applied to the X electrode **13** or the Y electrode **14**, an attracting force (electrostatic force) according to static electricity is generated between the X electrode **13** or the Y electrode **14** and the finger. In a case where an AC voltage is applied, the electrostatic force is periodically changed. As the electrostatic force is changed, a frictional force between the contact face **11** and the finger is periodically changed. When, the user traces the contact face **11** using his finger, a frictional force felt by the finger is periodically changed, and the user perceives a tactile sense. According to a conventional research, it has been disclosed that a tactile sense is perceived in a case where the frequency of an AC voltage is higher than 5 Hz and lower than 500 Hz, and a tactile sense is not perceived in a case where the frequency is not within this range.

(44) In a case where an AC voltage having the first frequency f_1 is applied to the X electrode **13**, and an AC voltage having the second frequency f_2 is applied to the Y electrode **14**, the electrostatic force is changed at the first frequency f_1 and the second frequency f_2 . In addition, a beat in which an electrostatic force is changed at the frequency of a difference between the first frequency f_1 and the second frequency f_2 is generated. According to a conventional research, it has been disclosed that a tactile sense according to a beat is perceived in a case where the frequency of the beat is higher than Hz and lower than 1000 Hz, and a tactile sense according to a beat is not perceived in a case where the frequency of the beat is not within this range.

(45) In this embodiment, the first frequency f_1 and the second frequency f_2 are set such that both the first frequency f_1 and the second frequency f_2 are 500 Hz or higher, and the absolute value of a

difference between the first frequency f_1 and the second frequency f_2 is more than 10 Hz and less than 1000 Hz. For example, the first frequency $f_1=1000$ Hz, and the second frequency $f_2=1240$ Hz. The X electrode driving circuit **23** connects some X electrodes **13** among the X electrodes **13** connected to the X electrode driving circuit **23** to the first AC voltage source **232** and connects the other X electrodes **13** to the ground under the control of the control circuit **21**. The Y electrode driving circuit **24** connects some Y electrodes **14** among the Y electrodes **14** connected to the Y electrode driving circuit **24** to the second AC voltage source **242** and connects the other Y electrodes **14** to the ground under the control of the control circuit **21**. For example, the tactile panel **1** includes five X electrodes X.sub.0 to X.sub.4 and six Y electrodes Y.sub.0 to Y.sub.5, the X electrode X.sub.1 is connected to the first AC voltage source **232**, the Y electrode Y.sub.1 is connected to the second AC voltage source **242**, and the X electrodes X.sub.0 and X.sub.2 to X.sub.4 and the Y electrodes Y.sub.0 and Y.sub.2 to Y.sub.5 are connected to the ground. In this case, at a portion of the contact face **11** at which the X electrode X.sub.1 and the Y electrode Y.sub.1 intersect with each other, a beat of 240 Hz is generated, and a user can perceive a tactile sense using his finger. At portions at which the X electrode X.sub.1 and the Y electrodes Y.sub.0 and Y.sub.2 to Y.sub.5 intersect with each other, while an electrostatic force is changed at the frequency of 1000 Hz, a tactile sense is not perceived. At portions at which the Y electrode Y.sub.1 and the X electrodes X.sub.0 and X.sub.2 to X.sub.4 intersect with each other, while an electrostatic force is changed at the frequency of 1240 Hz, a tactile sense is not perceived. At the other portions, an electrostatic force is not changed, and a tactile sense is not perceived. In this way, the tactile presentation device can present a tactile sense at an arbitrary position on the contact face **11**. In addition, a form in which the X electrode driving circuit **23** and the Y electrode driving circuit **24** connect the X electrodes **13** and the Y electrodes **14** not to the ground but to a predetermined DC power source may be employed.

(46) FIG. **6** is a schematic circuit diagram that illustrates the internal configuration of the touch panel driving circuit **22** according to Embodiment 1. The touch panel driving circuit **22** includes a plurality of signal input units **221** and a plurality of current detecting units **222**. Each of the signal input units **221** is connected to a signal line connected to the first switching unit **25**. Each of the current detecting units **222** is connected to a signal line connected to the second switching unit **26**. The signal input units **221** are connected to the X electrodes **13** through the first switching unit **25**, and the current detecting units **222** are connected to the Y electrodes **14** through the second switching unit **26**. The signal input unit **221** inputs an AC signal to a corresponding X electrode **13**. The current detecting unit **222** detects a current signal flowing through a corresponding Y electrode **14**. The internal circuit of the touch panel driving circuit **22** illustrated in FIG. **6** corresponds to a detection circuit.

(47) At each portion at which the X electrode **13** and the Y electrode **14** intersect with each other, electrostatic capacitance is generated between the X electrode **13** and the Y electrode **14**. In a case where the signal input unit **221** inputs an AC signal to the X electrode **13**, an AC current flows between the X electrode **13** and the Y electrode **14** to which the current detecting unit **222** is connected, and the current detecting unit **222** detects the AC current. On the contact face **11**, in a case where a user's finger is brought into contact with a portion facing a portion at which the X electrode **13** and the Y electrode **14** intersect with each other, electrostatic capacitance is generated between the X electrode **13** or the Y electrode **14** and the finger, and the electrostatic capacitance between the X electrode **13** and the Y electrode **14** changes. In a case where the electrostatic capacitance between the X electrode **13** and the Y electrode **14** changes, an AC current detected by the current detecting unit **222** changes. The operations of the first switching unit **25** and the second switching unit **26** are controlled by the control circuit **21**, and the X electrode **13** and the Y electrode **14** connected to the touch panel driving circuit **22** are specified under the control of the control circuit **21**. The control circuit **21** compares an AC current detected by the current detecting unit **222** with a predetermined threshold, thereby detecting a change in the electrostatic capacitance

between the X electrode **13** and the Y electrode **14** connected to the touch panel driving circuit **22**. In addition, the control circuit **21** detects the position with which the user's finger is brought into contact by specifying the X electrode **13** and the Y electrode **14** connected to the touch panel driving circuit **22** in a case where the electrostatic capacitance changes. The contact position on the contact face **11** is a position facing a portion at which the X electrode **13** and the Y electrode **14** connected to the touch panel driving circuit **22** intersecting with each other. The control circuit **21** outputs data representing the contact position to the arithmetic operation unit **31**. In this way, the tactile presentation device detects a contact position on the contact face **11** by using a mutual capacitance system.

(48) In addition, the tactile presentation device may employ a form in which not only a contact position on the contact face **11** is detected, but also a position at which an object approaches is detected in a case where the conductive object such as a finger approaches the contact face **11** within a predetermined distance. In such a form, in a case where an object approaches the contact face **11** within a predetermined distance, electrostatic capacitance is generated between the X electrode **13** and the object, and, similarly, a position approached by the object on the contact face **11** is detected. In addition, the touch panel driving circuit **22** may employ a form in which the current detecting unit **222** is connected to the X electrode **13**, and the signal input unit **221** is connected to the Y electrode **14**.

(49) Next, a process enabling both the detection of a contact position and the presentation of a tactile sense that is performed by the tactile presentation device will be described. The control circuit **21** performs control of the first switching unit **25** to connect each X electrode **13** to either the touch panel driving circuit **22** or the X electrode driving circuit **23**. Similarly, the control circuit **21** performs control of the second switching unit **26** to connect each Y electrode **14** to the touch panel driving circuit **22** or the Y electrode driving circuit **24**.

(50) The control circuit **21** causes the first switching unit **25** to connect some X electrodes **13** to the touch panel driving circuit **22** and connects the other X electrodes **13** to the X electrode driving circuit **23**. In addition, the control circuit **21** causes the first switching unit to sequentially change the X electrodes **13** to be connected to the touch panel driving circuit **22**. When the X electrode **13** connected to the touch panel driving circuit **22** is changed, the first switching unit **25** connects the X electrode **13** that has been connected to the touch panel driving circuit **22** until now to the X electrode driving circuit **23** and connects some X electrodes **13** among a plurality of X electrodes **13** that have been connected to the X electrode driving circuit **23** until now to the touch panel driving circuit **22**. For example, a state in which, among the X electrodes X.sub.0 to X.sub.4, the X electrode X.sub.0 is connected to the touch panel driving circuit **22**, and the X electrodes X.sub.1 to X.sub.4 are connected to the X electrode driving circuit **23** is changed to a state in which the X electrode X.sub.1 is connected to the touch panel driving circuit **22**, and the X electrodes X.sub.0 and X.sub.2 to X.sub.4 are connected to the X electrode driving circuit **23**. Then, similarly, the X electrode **13** connected to the touch panel driving circuit **22** is sequentially changed.

(51) Similarly, the control circuit **21** causes the second switching unit **26** to connect some Y electrodes **14** to the touch panel driving circuit **22** and connects the other Y electrodes **14** to the Y electrode driving circuit **24** and sequentially changes the Y electrode **14** to be connected to the touch panel driving circuit **22**. When the Y electrode **14** connected to the touch panel driving circuit **22** is changed, the second switching unit **26** connects the Y electrode **14** that has been connected to the touch panel driving circuit **22** until now to the Y electrode driving circuit **24** and connects some Y electrodes **14** among a plurality of Y electrodes **14** that have been connected to the Y electrode driving circuit **24** until now to the touch panel driving circuit **22**. For example, a state in which, among the Y electrodes Y.sub.0 to Y.sub.5, the Y electrode Y.sub.0 is connected to the touch panel driving circuit **22**, and the Y electrodes Y.sub.1 to Y.sub.5 are connected to the Y electrode driving circuit **24** is changed to a state in which the Y electrode Y.sub.1 is connected to the touch panel driving circuit **22**, and the Y electrodes Y.sub.0 and Y.sub.2 to Y.sub.5 are connected to the Y

electrode driving circuit **24**. Then, similarly, the Y electrode **14** connected to the touch panel driving circuit **22** is sequentially changed.

(52) In addition, the control circuit **21**, by controlling the single-pole double-throw switches **231** of the X electrode driving circuit **23**, connects the X electrode **13** corresponding to an area to which a tactile sense is to be presented to the first AC voltage source **232** and connects the other X electrodes **13** to the ground. Similarly, the control circuit **21**, by controlling the single-pole double-throw switches **241** of the Y electrode driving circuit **24**, connects the Y electrode **14** corresponding to an area to which a tactile sense is to be presented to the second AC voltage source **242** and connects the other Y electrodes **14** to the ground. For example, it is assumed that an area surrounded by two-dot chain lines illustrated in FIG. **3** is a target area **16** to which a tactile sense is to be presented on the contact face **11**, and the target area **16** is a portion facing intersections of the X electrodes X.sub.1 and X.sub.2 and the Y electrodes Y.sub.1 and Y.sub.2. In such a case, the X electrode driving circuit **23** connects the X electrodes X.sub.1 and X.sub.2 to the first AC voltage source **232** and connects the other X electrodes **13** to the ground, and the Y electrode driving circuit **24** connects the Y electrodes Y.sub.1 and Y.sub.2 to the second AC voltage source **242** and connects the other Y electrodes **14** to the ground.

(53) FIG. **7** is a timing diagram that illustrates an example of the operation of each electrode according to Embodiment 1. In FIG. **7**, the left side to the right side represent the elapse of time, and t.sub.0 to t.sub.13 represent respective time points. FIG. **7** illustrates the states of the X electrodes X.sub.0 to X.sub.4 and the Y electrodes Y.sub.0 to Y.sub.5 at each time point. A state in which the X electrode **13** or the Y electrode **14** is connected to the ground is denoted by T.sub.G, a state in which the X electrode **13** is connected to the first AC voltage source **232** is denoted by T.sub.A, and a state in which the Y electrode **14** is connected to the second AC voltage source **242** is denoted by TB. In addition, a state in which the X electrode **13** is connected to the touch panel driving circuit **22** is denoted by S.sub.T, and a state in which the Y electrode **14** is connected to the touch panel driving circuit **22** is denoted by S.sub.R.

(54) As illustrated in FIG. **7**, in a period of t.sub.0 to t.sub.6, the X electrode X.sub.0 is connected to the touch panel driving circuit **22**. In addition, in a period of t.sub.0 to t.sub.1, the Y electrode Y.sub.0 is connected to the touch panel driving circuit **22**, and, in a period of t.sub.1 to t.sub.2, the Y electrode Y.sub.1 is connected to the touch panel driving circuit **22**, and the like. Thus, each of the Y electrodes Y.sub.0 to Y.sub.5 is sequentially connected to the touch panel driving circuit **22**. Accordingly, in the period of t.sub.0 to t.sub.6, detection of contact at positions on the contact face **11** corresponding to intersections between the X electrode X.sub.0 and the Y electrodes Y.sub.0 to Y.sub.5 is sequentially performed. Similarly, in a period of t.sub.6 to t.sub.12, the X electrode X.sub.1 is connected to the touch panel driving circuit **22**, each of the Y electrodes Y.sub.0 to Y.sub.5 is sequentially connected to the touch panel driving circuit **22**, and detection of contact at positions on the contact face **11** corresponding to intersections between the X electrode X.sub.1 and the Y electrodes Y.sub.0 to Y.sub.5 is sequentially performed. The process is similarly repeated with the X electrode **13** connected to the touch panel driving circuit **22** changed, and the detection of contact at positions on the contact face **11** is sequentially performed. In this way, each of the X electrodes **13** and each of the Y electrodes **14** are sequentially connected to the touch panel driving circuit **22**, thereby being sequentially controlled for detection of contact on the contact face **11**. In other words, the contact face **11** is scanned for detection of a contact position. After the completion of the scanning of the whole contact face **11**, the control circuit **21** repeats the process of sequentially connecting each X electrode **13** and each Y electrode **14** to the touch panel driving circuit **22**. In this way, the scanning is repeated, and, in a case where a user contacts an arbitrary position on the contact face **11**, the contact point is detected. The scanning of the whole contact face **11** is repeated 10 to 1000 times per one second. For example, the scanning of the whole contact face **11** is repeated 60 times per one second.

(55) As illustrated in FIG. **7**, in a period other than the period in which the electrode is connected to

the touch panel driving circuit **22**, the X electrodes X.sub.1 and X.sub.2 are connected to the first AC voltage source **232**, and the Y electrodes Y.sub.1 and Y.sub.2 are connected to the second AC voltage source **242**, and the other X electrode **13** and the other Y electrodes **14** are connected to the ground. As a result, a tactile sense is presented to the target area **16** within the contact face **11**. In this way, the X electrodes **13** and the Y electrodes **14** are controlled for presenting a tactile sense to the contact face **11**. As a result of the control of the X electrodes **13** and the Y electrodes **14** as described above, a part of the contact face **11** is used for detecting contact, and the other portion is used for presenting a tactile sense, and the position of the portion used for detecting contact is sequentially changed. Each portion on the contact face **11** is used for detecting contact at a specific timing and is used for presenting a tactile sense at the other timings.

(56) As above, in this embodiment, also in a period in which some X electrodes **13** and some Y electrodes **14** are controlled for detecting contact on the contact face **11**, the other X electrodes **13** and Y electrodes **14** are controlled for presenting a tactile sense to the contact face **11**. For this reason, the tactile presentation device can simultaneously perform the presentation of a tactile sense and the detection of a contact position, and a tactile sense felt by a user during the use of the tactile presentation device is not interrupted. In addition, the X electrode **13** and the Y electrode **14** controlled for detecting contact on the contact face **11** are sequentially changed, and each of the X electrode **13** and the Y electrode **14** is controlled for presenting a tactile sense to the contact face **11** at timings other than the timing at which the electrodes are controlled for detecting contact. For this reason, contact can be detected at any position on the contact face **11**, and a tactile sense can be presented to any position. While the presentation of a tactile sense is not performed at a position at which the detection of contact on the contact face **11** is performed, the position at which the contact is detected is sequentially moved, and accordingly, the presentation of a tactile sense is not interrupted on the whole contact face **11**.

(57) As illustrated in FIG. 7, the control circuit **21** connects an X electrode **13** adjacent to the X electrode **13** connected to the touch panel driving circuit **22** among the X electrodes **13** to the X electrode driving circuit **23** through the first switching unit **25**. Similarly, the control circuit **21** connects a Y electrode **14** adjacent to the Y electrode **14** connected to the touch panel driving circuit **22** among the Y electrodes **14** to the Y electrode driving circuit **24** through the second switching unit **26**. In this way, the X electrode **13** that is adjacent to the X electrode **13** controlled for detecting contact on the contact face **11** and the Y electrode **14** adjacent to the Y electrode **14** controlled for detecting contact are controlled for presenting tactile senses. In a case where a plurality of electrodes controlled for detecting contact on the contact face **11** are adjacent to each other, there is a problem in that a portion not used for presenting a tactile sense becomes large. In this embodiment, electrodes adjacent to the electrodes controlled for detecting contact on the contact face **11** are controlled for presenting a tactile sense, and accordingly, the size of a portion not used for presenting a tactile sense on the contact face **11** is minimized.

(58) In this embodiment, a distance between the centers of the X electrodes **13** adjacent to each other and a distance between the centers of the Y electrodes **14** adjacent to each other are configured to be sufficiently smaller than an area in which a person's finger is brought into contact with the contact face **11**. For this reason, the size of a portion not used for presenting a tactile sense to the contact face **11** is sufficiently smaller than the size of a user's finger. In a portion in which a user's finger is brought into contact with the contact face **11**, even in a case where a part does not present a tactile sense, a tactile sense is presented to the other part, and a tactile sense averaged over the whole finger is perceived. Accordingly, a partly interruption of the presentation of a tactile sense for detecting a contact position is not perceived by a user.

(59) Conventionally, it is understood that the time resolution of a human's tactile sense is 10 ms. In this embodiment, a time interval for changing the X electrode **13** controlled for detecting contact on the contact face **11** is set to be shorter than 10 ms. In the example illustrated in FIG. 7, the length of the period of t.sub.0 to t.sub.6 and the length of the period of t.sub.6 to t.sub.12 is less than 10 ms.

For example, the length of a period in which each X electrode **13** is continuously connected to the touch panel driving circuit **22** is 1.6 ms. A time interval for changing the Y electrode **14** controlled for detecting contact on the contact face **11** is shorter. In the example illustrated in FIG. 7, the length of a period in which each Y electrode **14** is continuously connected to the touch panel driving circuit **22** is $\frac{1}{6}$ of the length of the period in which each X electrode **13** is continuously connected to the touch panel driving circuit **22**. The length of a period in which a tactile sense is not presented in a part of the contact face **11** is sufficiently shorter than the time resolution of the human tactile sense, and accordingly, a user cannot feel any loss of the tactile sense. Accordingly, a partly interruption of the presentation of a tactile sense for detecting a contact position cannot be perceived by a user.

(60) FIG. 8 is a timing diagram that illustrates another example of the operation of each electrode according to Embodiment 1. As illustrated in FIG. 8, the tactile presentation device may have a form in which a plurality of Y electrodes **14** are simultaneously connected to the touch panel driving circuit **22**. In this case, the control circuit **21** causes the second switching unit **26** to connect a plurality of Y electrodes **14** not adjacent to each other to the touch panel driving circuit **22**. More specifically, in a period of $t_{\text{sub.0}}$ to $t_{\text{sub.1}}$, Y electrodes $Y_{\text{sub.0}}$ and $Y_{\text{sub.4}}$ are connected to the touch panel driving circuit **22**, and, in a period of $t_{\text{sub.1}}$ to $t_{\text{sub.2}}$, Y electrodes $Y_{\text{sub.1}}$ and $Y_{\text{sub.5}}$ are connected to the touch panel driving circuit **22**. In other words, a plurality of Y electrodes **14** not adjacent to each other are controlled for simultaneously detecting contact on the contact face **11**.

(61) By simultaneously controlling the plurality of Y electrodes **14** for detecting contact on the contact face **11**, a time required for sequentially controlling all the Y electrodes **14** for detecting contact can be shortened. In accompaniment with this, a time required for controlling each X electrode **13** for detecting contact can be shortened. For this reason, a time required for detecting contact in all the portions of the contact face **11** can be shortened. In addition, the detection of contact is performed simultaneously at a plurality of positions on the contact face **11**. Accordingly, the tactile presentation device can quickly detect contact position in a case where a user contacts an arbitrary position on the contact face **11**. In addition, since the plurality of Y electrodes **14** controlled for detecting contact are not adjacent to each other, the size of a portion of the contact face **11** that is not used for presenting a tactile sense is minimized. Furthermore, the tactile presentation device may employ a form in which a plurality of X electrodes **13** not adjacent to each other are simultaneously controlled for detecting contact on the contact face **11**.

(62) Next, a distance between the centers of the electrodes adjacent to each other and a time interval for changing the electrode controlled for detecting contact on the contact face **11** will be further described. FIG. 9 is a schematic plan view that illustrates a model of the tactile panel **1** for description. A model in which a plurality of X electrodes **13** are arranged on the substrate **12**, but no Y electrode **14** is arranged will be considered. The number of the X electrodes **13** is assumed to be 32, and the distance between the centers of the X electrodes **13** adjacent to each other is assumed to be 5 mm. The size of the contact face **11** in the Y direction is 160 mm. A time for scanning all the X electrodes **13** is 16.6 ms. A time required for controlling each X electrode **13** for detecting contact is 0.519 ms. A contact portion where a user's finger touches the contact face **11** is a square of which the length of one side is 10 mm. The moving speed of a finger with contacting on the contact face **11** is 300 mm/s. An AC voltage applied to the X electrode **13** for presenting a tactile sense is a voltage of 150 V with 100 Hz.

(63) FIGS. 10A to 10D are schematic views that illustrate a positional relation between the X electrode **13** and a contact portion where a user's finger touches the contact face **11**. In the figures, a plurality of X electrodes **13** are vertically aligned, and an X electrode **131** illustrated in the figures represents an X electrode **13** controlled for detecting contact. X electrodes **13** other than the X electrode **131** are controlled for presenting a tactile sense. A contact portion **41** where the finger touches the contact face **11** is illustrated in the figures. In the figures, the downward direction is a Y

direction. States after predetermined times sequentially elapse from the state illustrated in FIG. 10A are respectively illustrated in FIGS. 10B, 10C, and 10D. In the figures, arrows illustrate directions in which the finger moves. As the user traces the contact face 11 in this direction by using a finger, a frictional force is generated between the finger and the contact face 11, and the user feels a tactile sense according to an electrostatic force. As illustrated in the sequence of FIGS. 10A to 10D, the contact portion 41 where the finger touches the contact face 11 moves according to elapse of time. Similarly, according to scanning, the position of the X electrode 131 controlled for detecting contact among the X electrodes 13 changes. The scanning speed of the X electrode 13 is much higher than the moving speed of the contact portion 41. As illustrated in FIG. 10C, in a case where the X electrode 131 and the contact portion 41 overlap each other in the plan view, contact of the finger is detected, and an electrostatic force operating on the finger for presenting a tactile sense is decreased.

(64) FIG. 11 is a schematic view that illustrates a relation between time and the positions of a contact portion 41 and an X electrode 131. In the drawing, the vertical axis represents time, and the time elapses from the upper side toward the lower side. The horizontal axis represents a position in the Y direction that is a distance from an end. In the drawing, each hatched portion represents that an X electrode 13 located at a position corresponding to the portion at time corresponding to the portion is an X electrode 131 controlled for detecting contact. The other portion represents that the X electrode 13 is controlled for presenting a tactile sense. For example, an X electrode 13 positioned in the first row, in other words, an X electrode 13 located at a position of 0 to 5 mm in the Y direction is controlled for detecting contact in a period of 0 to 0.519 ms and is controlled for presenting a tactile sense in the other period. An X electrode 13 positioned in the second row, in other words, an X electrode 13 located at a position of 5 to 10 mm in the Y direction is controlled for detecting contact in a period of 0.519 to 1.038 ms and is controlled for presenting a tactile sense in the other period. In this way, the X electrode 131 controlled for detecting contact is sequentially changed.

(65) In FIG. 11, the trajectory of the center of the contact portion 41 is illustrated using a solid line, and the trajectories of the upper end and the lower end of the contact portion 41 are illustrated using broken lines. At time 0, the center of the contact portion 41 is located at a position of 17.5 mm. This position coincides with the center of an X electrode 13 positioned in the fourth row in the Y direction. The user slides his finger on the contact face 11 at the speed of 300 mm/s in the Y direction in a direction in which the numerical value of the position of the Y direction increases. At time 5.19 ms, the position of the center of the contact portion 41 is 19.057 mm. As illustrated in FIG. 11, for example, at time 0.77 ms, the X electrodes 13 located at positions facing the range of the upper end to the lower end of the contact portion 41, in other words, the X electrodes 13 corresponding to all the areas of the contact portions 41 are controlled for presenting a tactile sense. At time 1.8 ms, X electrodes 13 corresponding to an area having a half area of the contact portion 41 are controlled for detecting contact, and the other X electrodes 13 are controlled for presenting a tactile sense. At this time, an electrostatic force generated at the finger for presenting a tactile sense becomes a half of a normal case in accordance with this area.

(66) FIG. 12 is a characteristic diagram that illustrates a change in the electrostatic force generated at a finger. The horizontal axis represents time, and the vertical axis represents a relative value of the electrostatic force. In a time period of 0 to 1.038 ms, the relative value of the electrostatic force is "1". After time 1.038 ms, the relative value of the static electric force decreases up to 0.775 and slightly rises up to 0.794 over time 1.557 ms. After time 1.557 ms, the relative value of the static electric force decreases up to 0.5 and is until time 2.076 ms. After time 2.076 ms, the relative value of the static electric force rises to 0.6935 and decreases up to 0.678 over time 2.595 ms. After time 2.595 ms, the relative value of the static electric force becomes 1. A period in which a decrease in the electrostatic force occurs is merely 1.557 ms between time 1.038 ms and time 2.595 ms. This period is sufficiently shorter than the time resolution 10 ms of the tactile sense. The minimum value

of the relative value of the electrostatic force is 0.5. As a result, an effect that an interruption of the tactile sense is not perceived by the user can be acquired.

(67) In addition, as the reason for user's no perception of an interruption of the tactile sense, another reason may be considered. In the model of the tactile panel **1** illustrated in FIG. **9**, the frequency of the AC voltage applied to the X electrode **13** for presenting a tactile sense is 100 Hz, and the frequency of the electrostatic force is 200 Hz, which is twice the frequency of the AC voltage. This frequency mainly stimulates a Pacinian corpuscle among human mechanoreceptors. The receptive field of the Pacinian corpuscle is wide, and an edge is unclearly detected or not detected. For this reason, even in a case where an electrostatic force is not generated in a half area of the contact portion **41**, it is perceived by the user that a tactile sense is presented to the whole contact portion **41**. Even in a case where a difference between a case where an electrostatic force is generated in the whole contact portion **41** and a case where an electrostatic force is generated only in a half thereof can be perceived, the difference is perceived as a difference in the strength of a stimulus, and a difference between presence/absence of an edge is not perceived. Since an edge that becomes a clue for the perception of a change in the tactile sense cannot be detected, the user cannot perceive a change in the tactile sense, and no interruption of the tactile sense is considered to be perceived. In this way, the use of the electrostatic force of a frequency mainly stimulating a Pacinian corpuscle is considered to be one factor causing the effect of user's no perception of an interruption of the tactile sense.

(68) Based on the viewpoints described above, in this embodiment, a distance between the centers of the X electrodes **13** adjacent to each other and a distance between the centers of the Y electrodes **14** adjacent to each other are 5 mm or less. In the contact portion where the finger touches the contact face **11**, a half or more in the X direction and a half or more in the Y direction face X electrodes **13** and Y electrodes **14** controlled for presenting a tactile sense. In addition, in this embodiment, a value acquired by integrating a function of a temporal change in the relative decreased amount of the electrostatic force within the contact portion **41** as illustrated in FIG. **12** with respect to time is configured to be less than 10 ms. Here, the concept of a value acquired by integrating the function of a temporal change in the relative decreased amount of the electrostatic force with respect to time will be supplemented. In FIG. **12**, the vertical axis represents the electrostatic force, in other words, a force, and the horizontal axis represents the time. Accordingly, a value acquired by integrating the function of a temporal change in the relative decreased amount of the electrostatic force with respect to time can be regarded as an analogy of an impulse called in dynamics. The magnitude of an interruption of the tactile sense perceived according to a decrease in the electrostatic force is a function of the magnitude of a decrease in the electrostatic force and a time in which the electrostatic force is decreased. The magnitude of the interruption of the tactile sense perceived in a predetermined range is a monotonous increasing function of an impulse that is the product of the magnitude of the decrease in the electrostatic force and the time in which the electrostatic force is decreased. By configuring the value acquired by integrating the function of the temporal change in the relative decreased amount of the electrostatic force with respect to time to be smaller than the time resolution, which is 10 ms, of the human tactile sense, the user's perception of an interruption in the presentation of a tactile sense disappears. In the example illustrated in FIG. **12**, a decrease in the electrostatic force occurs within a shorter period than 10 ms, which is the time resolution of a tactile sense, and a perceived electrostatic force is averaged over the whole finger to be non-zero even in the case where the electrostatic force is decreased, and accordingly, an interruption of the presentation of a tactile sense is not perceived by a user. In addition, even in a case where an average value of the electrostatic force over the whole finger is zero, by configuring the time in which the electrostatic force is zero to be shorter than 10 ms, an interruption of the presentation of a tactile sense is not perceived by the user.

(69) In the description of this embodiment presented above, while a form in which an electrode adjacent to an electrode controlled for detecting contact on the contact face **11** is an electrode

controlled next for detection of contact has been explained, the tactile presentation device may employ a form in which an electrode not adjacent to an electrode controlled for detection of contact is an electrode controlled next for the detection of contact. FIG. 13 is a schematic view that illustrates a relation between time and the positions of a contact portion 41 and an X electrode 131 in a case where the position of the X electrode 131 controlled for detecting contact is discretely changed in the model of the tactile panel 1 illustrated in FIG. 9. In the drawing, the vertical axis represents time, and the time elapses from the upper side toward the lower side. In the drawing, $T_{sub.s}$ is $T_{sub.s}=0.519$ ms. The horizontal axis represents a position in the Y direction that is a distance from an end. In the drawing, each hatched portion represents that an X electrode 13 located at a position corresponding to the portion at time corresponding to the portion is an X electrode 131 controlled for detecting contact. The other portion represents that the X electrode 13 is controlled for presenting a tactile sense.

(70) In the example illustrated in FIG. 13, in a time period of 0 to $T_{sub.s}$, an X electrode 13 located at a position of 0 to 5 mm in the Y direction, in other words, an X electrode 13 positioned in the first row is controlled for detection of contact. In a time period of $T_{sub.s}$ to $2 T_{sub.s}$, an X electrode 13 located at a position of 75 to 80 mm in the Y direction, in other words, an X electrode 13 positioned in the 16th row is controlled for detection of contact. Subsequently, in a time period of $2 T_{sub.s}$ to $3 T_{sub.s}$, an X electrode 13 located at a position of 10 to 15 mm in the Y direction, in other words, an X electrode 13 positioned in the 3rd row is controlled for detection of contact. In this way, the position of the X electrode 131 controlled for detection of contact is changed to the 16th row after the first row, and thereafter, is discretely changed to the 3rd row, the 18th row, the 5th row, the 20th row, the 7th row, and the like.

(71) By discretely changing the position of the X electrode 131, timings at which the electrostatic force decreases in a plurality of areas included within the contact portion 41 are discrete. For this reason, the period in which the presentation of the tactile sense is interrupted within the contact portion 41 is further shortened. Accordingly, the effect of user's no perception of an interruption of the tactile sense is further improved.

(72) In FIG. 13, two examples of the trajectories of the contact portion 41 are illustrated. The trajectory of the center of the contact portion 41 is illustrated using a solid line, and the trajectories of the upper end and the lower end of the contact portion 41 are illustrated using broken lines. The trajectories illustrated in a left portion of FIG. 13 are trajectories of a contact portion 41 that is located at the position of 17.5 mm at time 0 and moves at the speed of 300 mm/s in a direction in which the numerical value of the position of the Y direction increases. According to these trajectories, the electrostatic force within the contact portion 41 is 78% of a normal case in a time period of $2 T_{sub.s}$ to $3 T_{sub.s}$ and is 70% in a time period of $4 T_{sub.s}$ to $5 T_{sub.s}$. On the other hand, in a period interposed between both the periods, there is no decrease in the electrostatic force. The length of the period in which a decrease in the electrostatic force occurs is a maximum of $T_{sub.s}$ and is extremely short. The length of this period is shorter than 1.557 ms illustrated in FIG. 12 and is sufficiently shorter than 10 ms that is the time resolution of the tactile sense. For this reason, an interruption of the tactile sense is not perceived by the user. The trajectories illustrated in a right portion of FIG. 13 are trajectories of a contact portion 41 that is located at the position of 120 mm at time 0 and moves at the speed of 600 mm/s in a direction in which the numerical value of the position of the Y direction decreases. Also in the case of tracing these trajectories, the period in which a decrease in the electrostatic force occurs is a maximum of $T_{sub.s}$, which is extremely short, and an interruption of the tactile sense is not perceived by the user.

(73) As in the example illustrated in FIG. 13, the tactile presentation device may employ a form in which the positions of the X electrode 13 and the Y electrode 14 controlled for detecting contact on the contact face 11 may be discretely changed among the X electrodes 13 and the Y electrodes 14. By discretely changing the positions of the X electrode 13 and the Y electrode 14 to be controlled for detecting contact, timings at which the electrostatic force decreases in a plurality of areas

included within the contact portion **41** where the user's finger touches the contact face **11** are discrete. For this reason, similar to the example illustrated in FIG. **13**, the period in which the electrostatic force decreases within the contact portion is further shortened, and accordingly, the effect of user's no perception of an interruption of the tactile sense is further improved.

Embodiment 2

(74) A tactile presentation device according to Embodiment 2 detects a contact position on a contact face **11** by using a method difference from that of Embodiment 1. The configuration of the tactile presentation device is similar to that of the case of Embodiment 1 illustrated in FIGS. **1** to **3** except for the inside of a touch panel driving circuit **22**.

(75) FIG. **14** is a schematic circuit diagram that illustrates the internal configuration of the touch panel driving circuit **22** according to Embodiment 2. The touch panel driving circuit **22** includes a plurality of current detecting units **223** and a plurality of AC voltage sources **224**. Each current detecting unit **223** is connected to a signal line connected to a first switching unit **25** and is connected to a signal line connected to a second switching unit **26**. The AC voltage source **224** is connected to each current detecting unit **223**. The AC voltage sources **224** are connected to the ground. Through the first switching unit **25**, the current detecting units **223** are connected to X electrodes **13**, the AC voltage sources **224** apply voltages to the X electrodes **13**, and the current detecting units **223** detect currents flowing through the X electrodes **13**. Similarly, through the second switching unit **26**, the current detecting units **223** are connected to Y electrodes **14**, the AC voltage sources **224** apply voltages to the Y electrodes **14**, and the current detecting units **223** detect currents flowing through the Y electrodes **14**. The internal circuit of the touch panel driving circuit **22** illustrated in FIG. **14** corresponds to a detection circuit.

(76) In a state in which a user's finger is not brought into contact with the contact face **11**, even when voltages are applied from the AC voltage source **224** to the X electrodes **13** or the Y electrodes **14**, currents hardly flow, and currents detected by the current detecting units **223** are almost zero. More specifically, a slight current flows through the parasitic capacitance of each X electrode **13** and the parasitic capacitance of each Y electrode **14**. The current flowing through the parasitic capacitance is called a parasitic current. Each current detecting unit **223** detects a parasitic current. In a case where a user's finger is brought into contact with a portion on the contact face **11** that faces an X electrode **13** connected to the touch panel driving circuit **22**, electrostatic capacitance is generated between the X electrode **13** and the finger. An AC voltage is applied from the AC voltage source **224**, a current according to the electrostatic capacitance flows through the X electrode **13**, and the current detecting unit **223** detects the current. Similarly, electrostatic capacitance is generated between a user's finger brought into contact with the contact face **11** and the Y electrode **14** connected to the touch panel driving circuit **22**, a current according to the electrostatic capacitance flows through the Y electrode **14**, and the current detecting unit **223** detects the current. The norm of the current detected by the current detecting unit **223** is proportional to the generated electrostatic capacitance. In more details, an increased amount of the norm of the current detected by the current detecting unit **223** from a norm of a parasitic current is proportional to the generated electrostatic capacitance.

(77) The operations of the first switching unit **25** and the second switching unit **26** are controlled by a control circuit **21**, and the X electrode **13** and the Y electrode **14** connected to the touch panel driving circuit **22** are specified under the control of the control circuit **21**. The control circuit **21** detects generation of electrostatic capacitance in accordance with the norm of the current detected by the current detecting unit **223** being a predetermined value or more for each of the X electrodes **13** and the Y electrodes **14** connected to the touch panel driving circuit **22**. In addition, the control circuit **21** specifies the X electrode **13** and the Y electrode **14** in which the electrostatic capacitance is generated, in other words, the X electrode **13** and the Y electrode **14** connected to the touch panel driving circuit **22** when the electrostatic capacitance is generated, thereby detecting a position with which the user's finger is brought into contact. The contact position is a position on the contact face

11 that faces a portion at which the X electrode **13** and the Y electrode **14**, in which the electrostatic capacitance is generated, intersect each other. The control circuit **21** outputs data representing the contact position to an arithmetic operation unit **31**. In this way, the tactile presentation device detects a contact position on the contact face **11** by using a self capacitance system.

(78) In addition, the tactile presentation device may employ a form in which not only a contact position on the contact face **11** is detected but also a position at which an object approaches is detected in a case where the conductive object such as a finger approaches the contact face **11** within a predetermined distance. In such a form, in a case where an object approaches the contact face **11** within a predetermined distance, electrostatic capacitance is generated between the X electrode **13** and the Y electrode **14** and the object, and, similarly, a position approached by the object on the contact face **11** is detected.

(79) The control circuit **21**, similar to Embodiment 1, by controlling the first switching unit **25** and the second switching unit **26**, connects some X electrodes **13** and some Y electrodes **14** to the touch panel driving circuit **22** and sequentially changes the X electrodes **13** and the Y electrodes **14** connected to the touch panel driving circuit **22**. In addition, similar to Embodiment 1, the control circuit **21** connects the X electrodes **13** not connected to the touch panel driving circuit **22** to the X electrode driving circuit **23** and connects the Y electrodes **14** not connected to the touch panel driving circuit **22** to the Y electrode driving circuit **24**. In other words, also in this embodiment, some X electrodes **13** and some Y electrodes **14** are controlled for detecting contact on the contact face **11**, and the X electrodes **13** and the Y electrodes **14** controlled for detecting contact are sequentially changed, and each of the X electrodes **13** and the Y electrodes **14** is controlled for presenting a tactile sense to the contact face **11** at timings other than the timing at which the electrodes are controlled for detecting contact. For this reason, also in this embodiment, the tactile presentation device can simultaneously perform the presentation of a tactile sense and the detection of a contact position, and a tactile sense felt by a user during the use of the tactile presentation device is not interrupted.

(80) In Embodiments 1 and 2 described above, while a form in which the control circuit **21** is included in addition to the touch panel driving circuit **22**, the X electrode driving circuit **23**, the Y electrode driving circuit **24**, the first switching unit **25**, and the second switching unit **26** is illustrated, the tactile presentation device may employ a form not including the control circuit **21**. For example, the tactile presentation device may employ a form in which the touch panel driving circuit **22** has functions equivalent to those of the control circuit **21**. In addition, the tactile presentation device may employ a form in which the functions equivalent to those of the control circuit **21** are included in the touch panel driving circuit **22**, the X electrode driving circuit **23**, the Y electrode driving circuit **24**, the first switching unit **25**, and the second switching unit **26** in a distributed manner. Furthermore, the tactile presentation device may employ a form in which the operations of the touch panel driving circuit **22**, the X electrode driving circuit **23**, the Y electrode driving circuit **24**, the first switching unit **25**, and the second switching unit **26** are directly controlled by the arithmetic operation unit **31**.

(81) In Embodiments 1 and 2, while a form in which a tactile sense is presented using a beat between AC voltages applied to a specific X electrode **13** and a specific Y electrode **14** is illustrated, the tactile presentation device may employ a form in which a tactile sense is presented using a method other than methods that are generally known. For example, the tactile presentation device may employ a form in which a tactile sense is presented by applying the same AC voltage to a specific X electrode **13** and a specific Y electrode **14** or a form in which a tactile sense is presented by applying the same AC voltage to all the X electrodes **13** and all the Y electrodes **14**. In addition, the tactile presentation device may employ a form in which a tactile sense is presented by applying voltages having opposite polarities to the X electrodes **13** adjacent to each other or the Y electrodes **14** adjacent to each other.

(82) Furthermore, the tactile presentation device may employ a form in which a position at which

an object approaches or is in contact with the contact face **11** is detected using a generally-known method other than the methods described in Embodiments 1 and 2 described above. For example, the tactile presentation device may employ a form in which a current value of a voltage signal applied to the X electrode **13** and the Y electrode **14** for presenting a tactile sense is measured, and contact or approach of an object is detected according to a change in the measured current value. (83) In Embodiments 1 and 2, while a form in which the X electrodes **13** and the Y electrodes **14** are arranged such that the intersections of the X electrodes **13** and the Y electrodes **14** are arranged in a matrix pattern has been illustrated, the tactile presentation device may employ a form in which the X electrodes **13** and the Y electrodes **14** are arranged in any other form. For example, the tactile presentation device may employ a form in which the X electrodes **13** and the Y electrodes **14** are arranged such that the intersections of the X electrodes **13** and the Y electrodes **14** are arranged in a shape to be represented through a tactile sense.

Embodiment 3

(84) In Embodiment 3, a form is illustrated in which electrodes are arranged in a form different from those of Embodiments 1 and 2. The configuration of a tactile presentation device is similar to that of the case of Embodiment 1 illustrated in FIGS. 1 and 2 except for the insides of a tactile panel **1** and a tactile panel driving unit **2**.

(85) FIG. 15 is a block diagram that illustrates the internal configurations of the tactile panel **1** and the tactile panel driving unit **2** according to Embodiment 3. The tactile panel **1** includes a transparent substrate **12** such as a glass substrate, and a plurality of electrodes **17** are arranged on the substrate **12**. The shape of each electrode **17** is a rectangle, and the electrodes **17** are arranged in a matrix pattern. FIG. 15 illustrates an example in which the electrodes **17** are arranged in 6 rows x 9 columns. A wiring **18** is connected to each electrode **17**. In FIG. 15, while a reference numeral **17** is assigned to one electrode and a reference numeral **18** is assigned to one wiring, all the rectangular electrodes illustrated in FIG. 15 are electrodes **17**, and all the wirings connected to the electrodes **17** are wirings **18**. A direction along one row illustrated in FIG. 15 is set as an X direction, and a direction along one column is set as a Y direction. The plurality of electrodes **17** are insulated from each other. On the substrate **12**, a cover layer **15** having an insulating property is superimposed with the electrodes **17** interposed therebetween. The surface of the cover layer **15** is the contact face **11**.

(86) The tactile panel driving unit **2** includes a touch panel driving circuit (first control unit) **22** used for controlling the operations of the electrodes **17** for detecting contact on the contact face **11**. The tactile panel driving unit **2** includes an electrode driving circuit **27** used for controlling the operations of the electrodes **17** for presenting a tactile sense to the contact face **11**. The electrode driving circuit **27** corresponds to a second control unit. In addition, the tactile panel driving unit **2** includes a switching unit **28** to which a plurality of wirings **18** are connected. The electrodes **17** are connected to the switching unit **28** through the wirings **18**. The switching unit **28** connects some electrodes **17** to the touch panel driving circuit **22**, connects the other electrodes **17** to the electrode driving circuit **27**, and is configured to switch the connection of each electrode **17** to one side to the other side.

(87) The tactile panel driving unit **2** includes a control circuit **21**. The control circuit **21** is connected to the touch panel driving circuit **22**, the electrode driving circuit **27**, and the switching unit **28**. In addition, the control circuit **21** is connected to an arithmetic operation unit **31**. The control circuit **21** receives an input of a control signal from the arithmetic operation unit **31** and controls the operations of the touch panel driving circuit **22**, the electrode driving circuit **27**, and the switching unit **28**. The control circuit **21** and the switching unit **28** correspond to a third control unit.

(88) FIG. 16 is a schematic circuit diagram that illustrates the internal configuration of the electrode driving circuit **27** according to Embodiment 3. The electrode driving circuit **27** includes a plurality of single-pole double-throw switches **271** and an AC voltage source **272** that generates an

AC voltage having a predetermined frequency. The internal circuit of the electrode driving circuit 27 is configured to connect each wiring 18 connected through the switching unit 28 to one of the AC voltage source 272 and the ground by using each single-pole double-throw switch 271. Each single-pole double-throw switch 271 is controlled by the control circuit 21 and performs switching of a connection between each wiring 18 and the AC voltage source 272 or the ground. In other words, the electrode driving circuit 27 connects the electrode 17 connected through the switching unit 28 and the wiring 18 to one of the AC voltage source 272 and the ground, and switches the connection under the control of the control circuit 21. The internal circuit of the electrode driving circuit 27 illustrated in FIG. 16 corresponds to a signal applying circuit.

(89) The tactile presentation device presents a tactile sense to the contact face 11 by using the operation of the electrode driving circuit 27. In a case where an AC voltage is applied to an electrode 17 facing a user's finger brought into contact with the contact face 11, an electrostatic force that periodically changes is generated between the electrode 17 and the finger. When the user traces the contact face 11 by using a finger, a frictional force felt by the finger periodically changes, whereby a tactile sense is presented. The frequency of the AC voltage applied by the AC voltage source 272 is higher than 5 Hz and lower than 1000 Hz. For example, the frequency is 120 Hz. For this reason, a user can perceive a tactile sense on the contact face 11.

(90) The electrode driving circuit 27, under the control of the control circuit 21, connects some electrodes 17 among electrodes 17 connected to the electrode driving circuit 27 to the AC voltage source 272 and connects the other electrodes 17 to the ground. In a portion on the contact face 11 that faces the electrode 17 connected to the AC voltage source 272, a periodical electrostatic force is generated, and a user can perceive a tactile sense by using his finger. In the other portions, an electrostatic force is not generated, and a tactile sense is not perceived. In this way, the tactile presentation device can present a tactile sense at an arbitrary position of the contact face 11. The electrode driving circuit 27 may employ a form in which the electrodes 17 are connected not to the ground but a predetermined DC power source.

(91) FIG. 17 is a schematic circuit diagram that illustrates the internal configuration of the touch panel driving circuit 22 according to Embodiment 3. The touch panel driving circuit 22 includes a plurality of current detecting units 223 and a plurality of AC voltage sources 224. Each current detecting unit 223 is connected to a signal line connected to the switching unit 28. The AC voltage source 224 is connected to each current detecting unit 223. The AC voltage source 224 is connected to the ground. Through the switching unit 28 and a wiring 18, the current detecting unit 223 is connected to the electrode 17, the AC voltage source 224 applies a voltage to the electrode 17, and the current detecting unit 223 detects a current flowing through the electrode 17. The internal circuit of the touch panel driving circuit 22 illustrated in FIG. 17 corresponds to a detection circuit.

(92) In a state in which a user's finger is not brought into contact with the contact face 11, even when a voltage is applied from the AC voltage source 224 to the electrode 17, a current hardly flows, and a current detected by the current detecting unit 223 is almost zero. In more details, similar to Embodiment 2, the current detecting unit 223 detects a parasitic current. In a case where a user's finger is brought into contact with a portion on the contact face 11 that faces the electrode 17 connected to the touch panel driving circuit 22, electrostatic capacitance is generated between the electrode 17 and the finger. An AC voltage is applied from the AC voltage source 224, a current increased according to the electrostatic capacitance flows through the electrode 17, and the current detecting unit 223 detects the current. An increased amount of the norm of the current detected by the current detecting unit 223 is proportional to the generated electrostatic capacitance.

(93) The operation of the switching unit 28 is controlled by the control circuit 21, and the electrode 17 to be connected to the touch panel driving circuit 22 is specified under the control of the control circuit 21. The control circuit 21 detects generation of electrostatic capacitance in accordance with the norm of the current detected by the current detecting unit 223 being a predetermined value or more for each electrode 17 connected to the touch panel driving circuit 22. In addition, the control

circuit **21** specifies an electrode **17** in which the electrostatic capacitance is generated, in other words, an electrode **17** connected to the touch panel driving circuit **22** when the electrostatic capacitance is generated, thereby detecting a position with which the user's finger is brought into contact. The contact position is a position on the contact face **11** that faces the electrode **17** in which the electrostatic capacitance is generated. The control circuit **21** outputs data representing the contact position to the arithmetic operation unit **31**. In this way, the tactile presentation device detects a contact position on the contact face **11** by using a self-capacitance system.

(94) In addition, the tactile presentation device may employ a form in which not only a contact position on the contact face **11** is detected but also a position at which an object approaches is detected in a case where the conductive object such as a finger approaches the contact face **11** within a predetermined distance. In such a form, in a case where an object approaches the contact face **11** within a predetermined distance, electrostatic capacitance is generated between the electrode **17** and the object, and, similarly, a position approached by the object on the contact face **11** is detected.

(95) The control circuit **21** performs control of the switching unit **28** to connect each electrode **17** to either the touch panel driving circuit **22** or the electrode driving circuit **27**. The control circuit **21** causes the switching unit **28** to connect some electrodes **17** to the touch panel driving circuit **22** and connects the other electrodes **17** to the electrode driving circuit **27**. In addition, the control circuit **21** causes the switching unit **28** to sequentially change the electrodes **17** to be connected to the touch panel driving circuit **22**. When the electrode **17** connected to the touch panel driving circuit **22** is changed, the switching unit **28** connects the electrode **17** that has been connected to the touch panel driving circuit **22** until now to the electrode driving circuit **27** and connects some electrodes among a plurality of electrodes **17** that have been connected to the electrode driving circuit **27** until now to the touch panel driving circuit **22**. In addition, the control circuit **21**, by controlling the single-pole double-throw switch **271** of the electrode driving circuit **27**, connects an electrode **17** corresponding to an area to which a tactile sense is to be presented among the electrodes **17** connected to the electrode driving circuit **27** to the AC voltage source **272** and connects the other electrodes **17** to the ground.

(96) Under the control of the control circuit **21**, each of the plurality of electrodes **17** is sequentially connected to the touch panel driving circuit **22**, and detection of contact at a position on the contact face **11** that faces each electrode **17** is sequentially performed. By sequentially connecting each electrode **17** to the touch panel driving circuit **22**, each electrode **17** is sequentially controlled for detecting contact on the contact face **11**. In other words, the contact face **11** is scanned for detection of a contact position. After the completion of the scanning of the whole contact face **11**, the control circuit **21** repeats the process of sequentially connecting each electrode **17** to the touch panel driving circuit **22**. In this way, the scanning is repeated, and, in a case where a user contacts an arbitrary position on the contact face **11**, the contact point is detected. The scanning of the whole contact face **11** is repeated 10 to 1000 times per one second. For example, the scanning of the whole contact face **11** is repeated 120 times per one second. In a period other than the period in which the electrode **17** is connected to the touch panel driving circuit **22**, the electrode **17** is connected to the electrode driving circuit **27** under the control of the control circuit **21**. Some electrodes **17** are connected to the AC voltage source **272**, and the other electrodes **17** are connected to the ground. As a result, a tactile sense is presented to the contact face **11**. In this way, the electrodes **17** are controlled for presenting a tactile sense to the contact face **11**.

(97) FIG. **18** is a timing diagram that illustrates an example of a change in each electrode **17** state with respect to time according to Embodiment 3. The vertical axis represents the position of each electrode **17**. Numbers of 0 to 8 are assigned to the electrodes **17** disposed along the X direction, numbers of 0 to 5 are assigned to the electrodes **17** disposed along the Y direction, and the position of each electrode **17** is represented using a combination of an X-direction number and a Y-direction number. The horizontal axis represents the elapse of time, and, the elapse of time is represented by

attached numbers of 1 to 9 to periods dividing the time. The length of each period is 0.925 ms. In the drawing, each hatched portion represents that an electrode **17** located at a position corresponding to the portion in a period corresponding to the portion is controlled for detecting contact. The other portions represent that the electrodes **17** are controlled for presenting a tactile sense. A column of a period to which number “1” is assigned represents that state of each electrode **17** in a time period of 0 to 0.925 ms, and a column of a period to which number “2” is assigned represents that state of each electrode **17** in the next 0.925 ms. In the period to which number “1” is assigned, the electrodes **17** controlled for detecting contact are six electrodes **17** of which positions represented by (X, Y) are (0, 0), (0, 3), (3, 0), (3, 3), (6, 0), and (6, 3). The other electrodes **17** are controlled for presenting a tactile sense. In the period to which number “2” is assigned, the electrodes **17** controlled for detecting contact are six electrodes **17** of (0, 1), (0, 4), (3, 1), (3, 4), (6, 1), and (6, 4). As illustrated in FIG. **18**, in periods to which numbers “1” to “9” are assigned, all the electrodes **17** are sequentially controlled for presenting a tactile sense, and the scanning of the whole contact face **11** is completed in a time of 8.3 ms.

(98) As above, in this embodiment, also in a period in which some electrodes **17** are controlled for detecting contact on the contact face **11**, the other electrodes **17** are controlled for presenting a tactile sense to the contact face **11**. For this reason, the tactile presentation device can simultaneously perform the presentation of a tactile sense and the detection of a contact position. In addition, the electrode **17** controlled for detecting contact on the contact face **11** is sequentially changed, and each electrode **17** is controlled for presenting a tactile sense to the contact face **11** at timings other than the timing at which the electrode **17** is controlled for detecting contact. While the presentation of a tactile sense is not performed at a position at which the detection of contact on the contact face **11** is performed, the position at which the contact is detected is sequentially moved, and accordingly, the presentation of a tactile sense is not interrupted on the whole contact face **11**. Also in this embodiment, the tactile presentation device can simultaneously perform the presentation of a tactile sense and the detection of a contact position, and a tactile sense felt by a user during the use of the tactile presentation device is not interrupted.

(99) In addition, in this embodiment, the control circuit **21** causes the switching unit **28** to connect an electrode **17** adjacent to an electrode **17** connected to the touch panel driving circuit **22** to the electrode driving circuit **27**. In this way, the electrode **17** adjacent to the electrode **17** controlled for detecting contact on the contact face **11** is controlled for presenting a tactile sense. For this reason, the size of a portion not used for presenting a tactile sense on the contact face **11** is minimized.

(100) In the example illustrated in FIG. **18**, a plurality of electrodes **17** not adjacent to each other are simultaneously controlled for detecting contact on the contact face **11**. Accordingly, a time required for sequentially controlling all the electrodes **17** for detecting contact can be shortened, and a time required for scanning the whole contact face **11** can be shortened. In addition, since contact is detected simultaneously in a plurality of positions on the contact face **11**, the tactile presentation device can quickly detect contact positions.

(101) In this embodiment, a distance between the centers of the electrodes **17** adjacent to each other is configured to be sufficiently smaller than an area in which a person's finger is brought into contact with the contact face **11**. For example, in both the X direction and the Y direction, a distance between the centers of the electrodes **17** adjacent to each other is configured to be 5 mm. The size of a portion not used for presenting a tactile sense to the contact face **11** is sufficiently smaller than the size of a user's finger. In a portion in which a user's finger is brought into contact with the contact face **11**, even in a case where a part does not present a tactile sense, a tactile sense is presented to the other part, and a tactile sense averaged over the whole finger is perceived.

(102) In this embodiment, a time interval for changing the electrode **17** controlled for detecting contact on the contact face **11** is set to be shorter than 10 ms that is the time resolution of the tactile sense. In more details, a value acquired by integrating a function of a temporal change in the relative decreased amount of the electrostatic force in a portion in which the user's finger is brought

into contact with the contact face **11** with respect to time is configured to be less than 10 ms. For example, the control circuit **21** performs control of a time interval for changing the electrode **17** controlled for detecting contact to be less than 10 ms. In the example illustrated in FIG. **18**, a time interval for changing the electrode **17** controlled for detecting contact is 0.925 ms. A decrease in the electrostatic force occurs within a shorter period than the time resolution of the tactile sense, and, even in a case where the electrostatic force is decreased, the perceived electrostatic force is averaged over the whole finger not to be zero, and accordingly, an interruption of the presentation of a tactile sense is not perceived by the user.

(103) In FIG. **18**, while an example is illustrated in which an electrode **17** adjacent to the electrode **17** controlled for detecting contact on the contact face **11** is an electrode **17** controlled next for detecting contact, the tactile presentation device may employ a form in which the position of the electrode **17** controlled for detecting contact is discretely changed. By discretely changing the position of the electrode **17** controlled for detecting contact, timings at which the electrostatic force decreases in a plurality of areas included within the contact portion where the user's finger touches the contact face **11** are discrete. For this reason, the period in which the presented tactile sense is interrupted is further shortened, and the effect of user's no perception of an interruption of the tactile sense is further improved.

Fourth Embodiment 4

(104) A tactile presentation device according to Embodiment 4 detects a contact position on a contact face **11** by using a mutual capacitance system. The configuration of a tactile presentation device is similar to that of the case of Embodiment 1 illustrated in FIGS. **1** and **2** except for the insides of a tactile panel **1** and a tactile panel driving unit **2**. Similar to the case of Embodiment 3 illustrated in FIG. **15**, a tactile panel **1** includes: a substrate **12**, a plurality of rectangular electrodes **17** arranged on the substrate **12** in a matrix pattern; and a cover layer **15**. Similarly, the tactile panel driving unit **2**, as illustrated in FIG. **15**, includes: a touch panel driving circuit **22**; an electrode driving circuit **27**; a switching unit **28**; and a control circuit **21**.

(105) FIG. **19** is a schematic circuit diagram that illustrates the internal configurations of the touch panel driving circuit **22** and the switching unit **28** according to Embodiment 4. The plurality of electrodes **17** included in the tactile panel is configured by a plurality of electrode pairs each formed by one pair of electrodes **17** adjacent to each other. Each electrode **17** is connected to the switching unit **28** through a wiring **18**. The switching unit **28** is configured to connect some electrodes **17** to the touch panel driving circuit **22** and connect the other electrodes **17** to the electrode driving circuit **27** and to be able to switch the connection of each electrode **17** to one side to the other side. The switching unit **28** performs the switching in units of electrode pairs. In other words, two electrodes **17** included in an electrode pair have the connections to be simultaneously switched and are connected to a same circuit out of the touch panel driving circuit **22** and the electrode driving circuit **27**. The touch panel driving circuit **22** includes a plurality of signal input units **221** and a plurality of current detecting units **222**. The touch panel driving circuit **22** and the switching unit **28** are configured such that, when an electrode pair is connected to the touch panel driving circuit **22**, one electrode **17** is connected to the signal input unit **221**, and the other electrode **17** is connected to the current detecting unit **222**. The signal input unit **221** inputs an AC signal to one electrode **17**, and the current detecting unit **222** detects a current signal flowing through the other electrode **17**. The internal circuit of the touch panel driving circuit **22** illustrated in FIG. **19** corresponds to a detection circuit.

(106) Electrostatic capacitance is generated between two electrodes **17**, which are included in an electrode pair, adjacent to each other. In a case where the signal input unit **221** inputs an AC signal to one electrode **17**, an AC current flows between the two electrodes **17**, and the current detecting unit **222** detects the AC current. In a case where a user's finger is brought into contact with a portion on the contact face **11** that faces the electrode pair, electrostatic capacitance is generated between the electrode pair and the finger, and the electrostatic capacitance between the two

electrodes **17** changes. In a case where the electrostatic capacitance between the two electrodes **17** changes, the AC current detected by the current detecting unit **222** changes. The operation of the switching unit **28** is controlled by the control circuit **21**, and the electrode pair connected to the touch panel driving circuit **22** is specified under the control of the control circuit **21**. The control circuit **21** compares the AC current detected by the current detecting unit **222** with a predetermined threshold and detects that whether the electrostatic capacitance between the electrode pair connected to the touch panel driving circuit **22** has been changed. In a case where the electrostatic capacitance changes, the control circuit **21** specifies the electrode pair connected to the touch panel driving circuit **22**, thereby detecting a position with which the user's finger is brought into contact. The contact position is a position on the contact face **11** that faces the electrode pair connected to the touch panel driving circuit **22**. The control circuit **21** outputs data representing the contact position to the arithmetic operation unit **31**. In this way, the tactile presentation device detects a contact position on the contact face **11** by using a mutual capacitance system.

(107) In addition, the tactile presentation device may employ a form in which not only a contact position on the contact face **11** is detected but also a position at which an object approaches is detected in a case where the conductive object such as a finger approaches the contact face **11** within a predetermined distance. In such a form, in a case where an object approaches the contact face **11** within a predetermined distance, electrostatic capacitance is generated between the electrode pair and the object, and, similarly, a position approached by the object on the contact face **11** is detected.

(108) The configuration of the electrode driving circuit **27** is similar to that of Embodiment 3 illustrated in FIG. **16**. The control circuit **21** performs control of the switching unit **28** to connect each electrode pair to either the touch panel driving circuit **22** or the electrode driving circuit **27**. The control circuit **21** causes the switching unit **28** to connect some electrode pairs to the touch panel driving circuit **22** and connects the other electrode pairs to the electrode driving circuit **27**.

(109) In addition, the control circuit **21** causes the switching unit **28** to sequentially change the electrode pair to be connected to the touch panel driving circuit **22**. When the electrode pair connected to the touch panel driving circuit **22** is changed, the switching unit **28** connects the electrode pair that has been connected to the touch panel driving circuit **22** until now to the electrode driving circuit **27** and connects some electrode pairs among a plurality of electrode pairs that have been connected to the electrode driving circuit **27** until now to the touch panel driving circuit **22**. In addition, the control circuit **21**, by controlling the single-pole double-throw switches **271** of the electrode driving circuit **27**, connects an electrode **17** among the electrodes **17** connected to the electrode driving circuit **27** that corresponds to an area to which a tactile sense is to be presented to the AC voltage source **272** and connects the other electrodes **17** to the ground.

(110) Under the control of the control circuit **21**, each of the plurality of electrode pairs is sequentially connected to the touch panel driving circuit **22**, and detection of contact at a position on the contact face **11** that faces each electrode pair is sequentially performed. By sequentially connecting each electrode pair to the touch panel driving circuit **22**, each electrode pair is sequentially controlled for detecting contact on the contact face **11**. In other words, the contact face **11** is scanned for detection of a contact position. After the completion of the scanning of the whole contact face **11**, the control circuit **21** repeats the process of sequentially connecting each electrode pair to the touch panel driving circuit **22**. In this way, the scanning is repeated, and, in a case where a user contacts an arbitrary position on the contact face **11**, the contact point is detected. In a period other than the period in which an electrode **17** is connected to the touch panel driving circuit **22**, the electrode **17** is connected to the electrode driving circuit **27** under the control of the control circuit **21**. Some electrodes **17** are connected to the AC voltage source **272**, and the other electrodes **17** are connected to the ground. As a result, a tactile sense is presented to the contact face **11**. In this way, the electrodes **17** are controlled for presenting a tactile sense to the contact face **11**.

(111) FIG. **20** is a schematic view that illustrates an example of the tactile panel **1** according to

Embodiment 4. FIG. 20 illustrates an example in which the electrodes 17 are arranged in 4 rows x 6 columns. In FIG. 20, while a reference numeral 17 is assigned to one electrode, all the rectangular electrodes illustrated in FIG. 20 are electrodes 17. Numbers of 0 to 5 are assigned to the electrodes 17 disposed along the X direction, numbers of 0 to 3 are assigned to the electrodes 17 disposed along the Y direction, and the position of each electrode 17 is represented using a combination of an X-direction number and a Y-direction number. In the example illustrated in FIG. 20, an electrode 17 arranged in an even-numbered column and an electrode 17 arranged in the next column configure an electrode pair. For example, electrodes 17 located at positions (0, 0) and (1, 0) configure an electrode pair. Areas corresponding to the electrodes 17 located at positions of (1, 1), (1, 2), (2, 1), and (2, 2) are assumed to be target areas 16 to which a tactile sense is presented.

(112) FIG. 21 is a timing diagram that illustrates an example of the operation of each electrode 17 according to Embodiment 4. In FIG. 21, the left side to the right side represent the elapse of time, and $t_{sub.0}$ to $t_{sub.12}$ represent respective time points. FIG. 21 illustrates the states of electrodes 17 of which positions are represented as (X, Y) at each time point. FIGS. 22A to 22C are schematic views that illustrate the states of the tactile panel 1 at specific timings according to Embodiment 4. FIGS. 22A, 22B, and 22C respectively illustrate the states of periods of $t_{sub.1}$ to $t_{sub.2}$, $t_{sub.2}$ to $t_{sub.3}$, and $t_{sub.3}$ to $t_{sub.4}$. A state in which the electrode 17 is connected to the ground is denoted by $T_{sub.G}$, a state in which the electrode 17 is connected to the AC voltage source 272 is denoted by $T_{sub.D}$, a state in which the electrode 17 is connected to the signal input unit 221 is denoted by $S_{sub.T}$, and a state in which the electrode 17 is connected to the current detecting unit 222 is denoted by $S_{sub.R}$.

(113) As illustrated in FIGS. 21 and 22A to 22C, in a period of $t_{sub.1}$ to $t_{sub.2}$, electrode pairs located at positions of (2, 0) and (3, 0) and electrode pairs located at positions of (4, 2) and (5, 2) are controlled for detecting contact. In a period of $t_{sub.2}$ to $t_{sub.3}$, electrode pairs located at positions of (4, 0) and (5, 0) and electrode pairs located at positions of (0, 3) and (1, 3) are controlled for detecting contact. In a period of $t_{sub.3}$ to $t_{sub.4}$, electrode pairs located at positions of (0, 1) and (1, 1) and electrode pairs located at positions of (2, 3) and (3, 3) are controlled for detecting contact. In this way, each electrode pair is sequentially controlled for detecting contact, and detection of contact at each position on the contact face 11 is sequentially performed. In addition, in periods other than the periods in which the electrode pairs are controlled for detecting contact, electrode 17 located at positions of (1, 1), (1, 2), (2, 1), and (2, 2) are connected to the AC voltage source 272, and the other electrodes 17 are connected to the ground. As a result, a tactile sense is presented to a target area 16 within the contact face 11.

(114) As above, also in this embodiment, in a period in which some electrodes 17 are controlled for detecting contact on the contact face 11, the other electrodes 17 are controlled for presenting a tactile sense to the contact face 11. For this reason, the tactile presentation device can simultaneously perform the presentation of a tactile sense and the detection of a contact position. In addition, the electrode 17 controlled for detecting contact on the contact face 11 is sequentially changed, and each electrode 17 is controlled for presenting a tactile sense to the contact face 11 at timings other than the timing at which the electrode 17 is controlled for detecting contact. While the presentation of a tactile sense is not performed at a position at which the detection of contact on the contact face 11 is performed, the position at which the contact is detected is sequentially moved, and accordingly, the presentation of a tactile sense is not interrupted on the whole contact face 11. Similar to Embodiment 3, a decrease in the electrostatic force occurs within a shorter period than the time resolution of a tactile sense, and a perceived electrostatic force is averaged over the whole finger to be non-zero even in a case where the electrostatic force is decreased, and accordingly, an interruption of the presentation of a tactile sense is not perceived by a user. Accordingly, also in this embodiment, the tactile presentation device can simultaneously perform the presentation of a tactile sense and the detection of a contact position, and a tactile sense felt by a user during the use of the tactile presentation device is not interrupted.

(115) In Embodiments 3 and 4 described above, while a form in which the control circuit **21** is included in addition to the touch panel driving circuit **22**, the electrode driving circuit **27**, and the switching unit **28** is illustrated, the tactile presentation device may employ a form not including the control circuit **21**. For example, the tactile presentation device may employ a form in which the touch panel driving circuit **22** has functions equivalent to those of the control circuit **21** or a form in which the functions equivalent to those of the control circuit **21** are included in the touch panel driving circuit **22**, the electrode driving circuit **27**, and the switching unit **28** in a distributed manner. Furthermore, the tactile presentation device may employ a form in which the operations of the touch panel driving circuit **22**, the electrode driving circuit **27**, and the switching unit **28** are directly controlled by the arithmetic operation unit **31**.

(116) In Embodiments 3 and 4, while a form in which a tactile sense is presented by applying an AC voltage to a specific electrode **17** is illustrated, the tactile presentation device may employ a form in which a tactile sense is presented using a method other than methods that are generally known. For example, the tactile presentation device may employ a form in which a tactile sense is presented by applying the same AC voltage to all the electrodes **17**. In addition, the tactile presentation device may employ a form in which a tactile sense is presented by applying voltages having opposite polarities to the electrodes **17** adjacent to each other.

(117) Furthermore, the tactile presentation device may employ a form in which a position at which an object approaches or is in contact with the contact face **11** is detected using a generally-known method other than the methods described in Embodiments 3 and 4. For example, the tactile presentation device may employ a form in which a current value of a voltage signal applied to the electrodes **17** for presenting a tactile sense is measured, and contact or approach of an object is detected according to a change in the measured current value. In Embodiments 3 and 4, while a form in which the electrodes **17** are arranged in a matrix pattern has been illustrated, the tactile presentation device may employ a form in which the electrodes **17** are arranged in any other form. For example, the tactile presentation device may employ a form in which the electrodes **17** are arranged in a shape to be represented through a tactile sense.

Embodiment 5

(118) FIG. **23** is a block diagram that illustrates the internal configuration of a tactile panel **1** according to Embodiment 5. The configuration of a tactile presentation device according to Embodiment is similar to that of Embodiment 1 or 2 except for the tactile panel **1**. An X electrode **13** is configured by a plurality of sub X electrodes **132**, and a Y electrode **14** is configured by a plurality of sub Y electrodes **142**. The plurality of sub X electrodes **132** configuring the X electrode **13** are arranged in parallel to be adjacent to each other and are commonly connected. Similarly, the plurality of sub Y electrodes **142** configuring the Y electrode **14** are arranged in parallel to be adjacent to each other and are connected to each other. In the drawing, while an example in which the X electrode **13** is configured by three sub X electrodes **132** is illustrated, the X electrode **13** may be configured by two sub X electrodes **132** or four or more sub X electrodes **132**. Similarly, the Y electrode **14** may be configured by two sub Y electrodes **142** or four or more sub Y electrodes **142**. The other configurations of the tactile panel **1** are similar to those of Embodiment 1 or 2.

(119) The operation of the tactile presentation device according to this embodiment is similar to that according to Embodiment 1 or 2. In other words, some of the X electrodes **13** and the Y electrodes **14** are controlled for detecting a position at which an object is in contact with or approaches a contact face **11**, and the X electrode **13** and the Y electrode **14** controlled for detecting a contact position or an approaching position of the object are sequentially changed. At timings other than a timing at which each of X electrodes **13** and Y electrodes **14** is controlled for detecting contact, each of X electrodes **13** and Y electrodes **14** is controlled for presenting a tactile sense to the contact face **11**. In this way, a plurality of sub X electrodes **132**, which configure one X electrode **13**, adjacent to each other and a plurality of sub Y electrodes **142**, which configure one Y electrode **14**, adjacent to each other are used for detecting a position, and the other sub X electrodes

132 and the other sub Y electrode **142** are used for presenting a tactile sense. Similar to Embodiments 1 and 2, also in this embodiment, the tactile presentation device can simultaneously perform the presentation of a tactile sense and the detection of a contact position, and a tactile sense felt by a user during the use of the tactile presentation device is not interrupted.

(120) It is preferable that a distance between the centers of a plurality of sub X electrodes **132** configuring X electrodes **13** in the Y direction between the X electrodes **13** adjacent to each other is less than 10 mm such that the sub X electrode **132** used for detecting a position and the sub X electrode **132** used for presenting a tactile sense are included inside a contact portion where a user's finger touches the contact face **11**. It is more preferable that this distance is less than 6 mm.

Similarly, a distance between the centers of a plurality of sub Y electrodes **142** configuring Y electrodes **14** in the X direction between the Y electrodes **14** adjacent to each other is preferably less than 10 mm and is more preferably less than 6 mm.

Embodiment 6

(121) Embodiment 6 is a modification of Embodiment 2. In Embodiment 2, in a case where a voltage is applied from the AC voltage source **224** to the X electrode **13** or the Y electrode **14** in a state in which a user's finger is not brought into contact with the contact face **11**, parasitic currents flow through the parasitic capacitance of each X electrode **13** and the parasitic capacitance of each Y electrode **14**, and the current detecting unit **223** detects these parasitic currents. The parasitic capacitance of an X electrode **13** is formed between the X electrode **13** and a plurality of Y electrodes **14** intersecting with the X electrode **13** and between the X electrode **13** and an X electrode **13** adjacent to the X electrode **13**. The parasitic capacitance of a Y electrode **14** is formed between the Y electrode **14** and a plurality of X electrodes **13** intersecting with the Y electrode **14** and between the Y electrode **14** and a Y electrode **14** adjacent to the Y electrode **14**. Depending on the design of the tactile panel **1**, the value of such parasitic capacitance becomes large, and there is concern that a parasitic currents flowing through the parasitic capacitance causes a problem. Since the parasitic current may occupy most of the dynamic range of a current value that can be detected by the current detecting unit, it is preferable to decrease the parasitic current. Embodiment 6 is a form for decreasing the parasitic current.

(122) FIG. **24** is a block diagram that illustrates the internal configurations of a tactile panel **1** and a tactile panel driving unit **2** according to Embodiment 6. An X electrode driving circuit **23** is connected to a touch panel driving circuit **22**. In addition, a Y electrode driving circuit **24** is connected to the touch panel driving circuit **22**. As will be described later, the internal configurations of the touch panel driving circuit **22**, the X electrode driving circuit **23**, and the Y electrode driving circuit **24** are different from those according to Embodiment 1 and 2. The touch panel driving circuit **22** can supply a voltage generated by an internal AC voltage source to the X electrode driving circuit **23** and the Y electrode driving circuit **24**. The other parts of the tactile presentation device are similar to those according to Embodiment 1.

(123) FIG. **25** is a schematic circuit diagram that illustrates the internal configuration of the touch panel driving circuit **22** according to Embodiment 6. The touch panel driving circuit **22** includes an AC voltage source **225**. The AC voltage source **225** is connected to a plurality of current detecting units **223**. In addition, the AC voltage source **225** is connected to the X electrode driving circuit **23** and the Y electrode driving circuit **24**. A high pass filter (HPF) **226** is disposed between the current detecting unit **223** and a first switching unit **25**. In addition, a high pass filter **226** is disposed between the current detecting unit **223** and a second switching unit **26**. The AC voltage source **225** generates an AC voltage having a higher frequency than that of a first AC voltage source **232** included in the X electrode driving circuit **23** and a second AC voltage source **242** included in the Y electrode driving circuit **24**. The high pass filter **226** has characteristics for transmitting a current having the same frequency (for example, 100 kHz) as that of an AC voltage generated by the AC voltage source **225** and blocking a current having the same frequency (for example, 1000 Hz and 1240 Hz) as that of an AC voltage generated by the first AC voltage source **232** and the second AC

voltage source **242**. The other parts of the touch panel driving circuit **22** are similar to those according to Embodiment 1.

(124) FIG. **26** is a schematic circuit diagram that illustrates the internal configuration of the X electrode driving circuit **23** according to Embodiment 6. As described above, the AC voltage source **225** included in the touch panel driving circuit **22** is connected to the X electrode driving circuit **23**. The X electrode driving circuit **23** includes a voltage superimposing unit **233** that superimposes a voltage generated by the AC voltage source **225** on a voltage generated by the first AC voltage source **232**. In addition, the X electrode driving circuit **23** includes a voltage superimposing unit **234** that superimposes the voltage generated by the AC voltage source **225** on the ground voltage. Each single-pole double-throw switch **231** performs switching of a connection between each X electrode **13** and an output node N1 of the voltage superimposing unit **233** or an output node N2 of the voltage superimposing unit **234**. The other parts of the X electrode driving circuit **23** are similar to those according to Embodiment 1.

(125) The operations of the voltage superimposing unit **233** and the voltage superimposing unit **234** will be described. FIGS. **27A** to **27D** are graphs that schematically illustrate the waveforms of voltages acquired by the X electrode driving circuit **23** according to Embodiment 6. In the drawing, the horizontal axis represents the time, and the vertical axis represents the voltage. The amplitude of the AC voltage generated by the first AC voltage source **232** is assumed to be 100 V, and a first frequency f_1 is assumed to be 1000 Hz. The amplitude of the AC voltage generated by the AC voltage source **225** of the touch panel driving circuit **22** is assumed to be 1 V, and the frequency is assumed to be 100 kHz. FIG. **27A** schematically illustrates the waveform of the AC voltage generated by the first AC voltage source **232**, and FIG. **27B** schematically illustrates the waveform of the AC voltage generated by the AC voltage source **225**. FIG. **27C** schematically illustrates the waveform of a voltage output by the output node N1 of the voltage superimposing unit **233**. The voltage output from the output node N1 is a voltage acquired by adding the AC voltage generated by the first AC voltage source **232** and the AC voltage generated by the AC voltage source **225**. FIG. **27D** schematically illustrates the waveform of a voltage output by the output node N2 of the voltage superimposing unit **234**. The voltage output from the output node N2 is a voltage acquired by adding the voltage of the ground, for example, a voltage of 0 V and the AC voltage generated by the AC voltage source **225**. In this way, the voltage superimposing unit **233** and the voltage superimposing unit **234** have a function of adding given two voltages and outputting a resultant voltage.

(126) FIG. **28** is a schematic circuit diagram that illustrates the internal configuration of the Y electrode driving circuit **24** according to Embodiment 6. As described above, the AC voltage source **225** included in the touch panel driving circuit **22** is connected to the Y electrode driving circuit **24**. The Y electrode driving circuit **24** includes a voltage superimposing unit **243** that superimposes the voltage generated by the AC voltage source **225** on the voltage generated by the second AC voltage source **242**. In addition, the Y electrode driving circuit **24** includes a voltage superimposing unit **244** that superimposes the voltage generated by the AC voltage source **225** on the ground voltage. Each single-pole double-throw switch **241** performs switching of a connection between each Y electrode **14** and an output node N3 of the voltage superimposing unit **243** or an output node N4 of the voltage superimposing unit **244**. The other parts of the Y electrode driving circuit **24** are similar to those according to Embodiment 1.

(127) The operations of the voltage superimposing unit **243** and the voltage superimposing unit **244** will be described. FIGS. **29A** to **29D** are graphs that schematically illustrate the waveforms of voltages acquired by the Y electrode driving circuit **24** according to Embodiment 6. In the drawing, the horizontal axis represents the time, and the vertical axis represents the voltage. The amplitude of the AC voltage generated by the second AC voltage source **242** is assumed to be 100 V, and a second frequency f_2 is assumed to be 1240 Hz. The amplitude of the AC voltage generated by the AC voltage source **225** of the touch panel driving circuit **22** is assumed to be 1 V, and the frequency

is assumed to be 100 kHz. FIG. 29A schematically illustrates the waveform of the AC voltage generated by the second AC voltage source 242, and FIG. 29B schematically illustrates the waveform of the AC voltage generated by the AC voltage source 225. FIG. 29C schematically illustrates the waveform of a voltage output by the output node N3 of the voltage superimposing unit 243. The voltage output from the output node N3 is a voltage acquired by adding the AC voltage generated by the second AC voltage source 242 and the AC voltage generated by the AC voltage source 225. FIG. 29D schematically illustrates the waveform of a voltage output by the output node N4 of the voltage superimposing unit 244. The voltage output from the output node N4 is a voltage acquired by adding the voltage of the ground, for example, a voltage of 0 V and the AC voltage generated by the AC voltage source 225. In this way, the voltage superimposing unit 243 and the voltage superimposing unit 244 have a function of adding given two voltages and outputting a resultant voltage.

(128) In Embodiment 2, the X electrode 13 is connected to one of the first AC voltage source 232, the ground, and the touch panel driving circuit 22. In contrast to this, in Embodiment 6, the X electrode 13 is connected to one of the output node N1 of the voltage superimposing unit 233, the output node N2 of the voltage superimposing unit 234, and the touch panel driving circuit 22. In a state in which the X electrode 13 is connected to the touch panel driving circuit 22, as illustrated in FIG. 27B, the AC voltage generated by the AC voltage source 225 is applied to the X electrode 13. In a state in which the X electrode 13 is connected to the output node N1, as illustrated in FIG. 27C, a voltage acquired by adding the AC voltage generated by the first AC voltage source 232 and the AC voltage generated by the AC voltage source 225 is applied to the X electrode 13. In a state in which the X electrode 13 is connected to the output node N2, as illustrated in FIG. 27D, a voltage acquired by adding the voltage of the ground voltage and the AC voltage generated by the AC voltage source 225 is applied to the X electrode 13.

(129) In Embodiment 2, the Y electrode 14 is connected to one of the second AC voltage source 242, the ground, and the touch panel driving circuit 22. In contrast to this, in Embodiment 6, the Y electrode 14 is connected to one of the output node N3 of the voltage superimposing unit 243, the output node N4 of the voltage superimposing unit 244, and the touch panel driving circuit 22. In a state in which the Y electrode 14 is connected to the touch panel driving circuit 22, as illustrated in FIG. 29B, the AC voltage generated by the AC voltage source 225 is applied to the Y electrode 14. In a state in which the Y electrode 14 is connected to the output node N3, as illustrated in FIG. 29C, a voltage acquired by adding the AC voltage generated by the second AC voltage source 242 and the AC voltage generated by the AC voltage source 225 is applied to the Y electrode 14. In a state in which the Y electrode 14 is connected to the output node N4, as illustrated in FIG. 29D, a voltage acquired by adding the voltage of the ground voltage and the AC voltage generated by the AC voltage source 225 is applied to the Y electrode 14.

(130) The voltage superimposing units 233, 234, 243, and 244 are configured such that the amplitudes of components of the frequency (in this embodiment 100 kHz) of the voltages generated by the AC voltage source 225 of the touch panel driving circuit 22 are the same in the voltages applied to the X electrode 13 and the Y electrode 14. In other words, voltages including a component having the same frequency and the same amplitude as those of the voltage applied to the X electrode 13 and the Y electrode 14 connected to the touch panel driving circuit 22 are applied to the X electrode 13 connected to the output node N1, the X electrode 13 connected to the output node N2, the Y electrode 14 connected to the output node N3, and the Y electrode 14 connected to the output node N4. When the frequency component of the voltage generated by the AC voltage source 225 of the touch panel driving circuit 22 is focused in the voltages applied to the X electrode 13 and the Y electrode 14, all the X electrodes 13 and the Y electrodes 14 are driven with the same amplitude and the same phase. For this reason, in a case where a voltage is applied from the AC voltage source 225 to the X electrode 13 or the Y electrode 14 in a state in which a user's finger is not brought into contact with the contact face 11, a voltage between the electrodes

configuring parasitic capacitance is constant, and no current flows through the parasitic capacitance.

(131) Here, the tactile panel **1**, as illustrated in FIG. **24**, is assumed to include five X electrodes X.sub.0 to X.sub.4 and six Y electrodes Y.sub.0 to Y.sub.5, and a state in which the X electrode X.sub.1 is connected to the touch panel driving circuit **22** will be considered. At this time, in the X electrode X.sub.1, intersections of the X electrode X.sub.1 and the Y electrodes Y.sub.0 to Y.sub.5, an adjacent portion between the X electrode X.sub.1 and the X electrode X.sub.0, and an adjacent portion between the X electrode X.sub.1 and the X electrode X.sub.2, parasitic capacitance is formed. In addition, the X electrode X.sub.1 is connected to the AC voltage source **225** through the current detecting unit **223**, and the voltage generated by the AC voltage source **225** is superimposed in all the other electrodes.

(132) FIG. **30** is a circuit diagram acquired by modeling a state in which the X electrode X.sub.1 is connected to the AC voltage source **225** through the current detecting unit **223**, and a voltage generated by the AC voltage source **225** is superimposed in all the other electrodes. The X electrode X.sub.1 corresponds to an electrode P1 in the drawing, and all the other electrodes correspond to an electrode P2 in the drawing. Parasitic capacitance C_p is present between the electrodes P1 and P2. However, since an electric potential difference between the electrode P1 and the electrode P2 configuring the parasitic capacitance C_p does not change, a current of the component of the frequency of the voltage generated by the AC voltage source **225** does not flow through the parasitic capacitance C_p . For this reason, the current detecting unit **223** does not detect any current.

(133) FIG. **31** is a circuit diagram that models the states of the electrodes according to Embodiment 2. In Embodiment 2, the X electrode X.sub.1 is connected to the AC voltage source **224** having a frequency of 100 kHz through the current detecting unit **223**, and most of the other electrodes are connected to the ground, the first AC voltage source **232** having a frequency of 1000 Hz, or the second AC voltage source **242** having a frequency of 1240 Hz. When the component of 100 kHz that is the frequency of the voltage generated by the AC voltage source **224** is focused, the state can be represented as a model in which most of the electrodes other than the X electrode X.sub.1 are connected to the ground. The electrode P1 illustrated in FIG. **31** corresponds to the X electrode X.sub.1, and the electrode P2 corresponds to an electrode of combining most of the other electrodes. Since an electric potential difference between the electrode P1 and the electrode P2 configuring the parasitic capacitance C_p changes, a current flows through the parasitic capacitance C_p . This current is a parasitic current that flows in a state in which a user's finger is not brought into contact with the contact face **11** in Embodiment 2.

(134) The parasitic capacitance was measured in the tactile panel **1** according to Embodiment 6 that was actually produced, and the parasitic capacitance of one X electrode **13** was 240 pF, and the parasitic capacitance of one Y electrode **14** was 170 pF. In addition, in a case where a user's finger was brought into contact with the contact face **11**, electrostatic capacitance between the electrode and the finger was 5 pF. In Embodiment 2, 240/245 of the dynamic range of the current value that can be detected by the current detecting unit **223** is occupied by a parasitic current that is basically unnecessary. In contrast to this, in Embodiment 6, the parasitic current is decreased to be almost zero, and the SN ratio of the current detected by the current detecting unit **223** is improved.

(135) FIG. **32** is a circuit diagram that illustrates an example of the configuration of the voltage superimposing units **233** and **234** according to Embodiment 6. The voltage superimposing unit **233** is configured by a capacitor C1. One end of the capacitor C1 is connected to the output node N1, and the other end is connected to the AC voltage source **225** of the touch panel driving circuit **22**. The first AC voltage source **232** is connected to the one end of the capacitor C1 and the output node N1. Resistance R1 denoted inside the first AC voltage source **232** represents the output impedance of the first AC voltage source **232**. The voltage superimposing unit **234** includes a resistor R3 connected between the output node N2 and the ground, and a resistor R2 connected

between the output node N2 and the AC voltage source 225. The ratio between the resistor R2 and the resistor R3 is set such that, in voltages output from the output node N1 and the output node N2, the amplitudes of components of the frequency of the voltage generated by the AC voltage source 225 are the same. The voltage superimposing units 243 and 244 are similarly configured.

(136) The configuration of the tactile presentation device for decreasing a parasitic current described in Embodiment 6 described above may be applied to Embodiment 3 in which a plurality of electrodes arranged in a matrix pattern are included. Also in the form in which the configuration for decreasing a parasitic current is applied to Embodiment 3, effects similar to those according to Embodiment 6 can be acquired. In addition, the configuration for decreasing a parasitic current described in Embodiment 6 may be applied to a tactile presentation device not including the third control unit. In other words, also in a tactile presentation device in which electrodes used for presenting a tactile sense and electrodes used for detecting contact or approach of an object are separately arranged along the contact face, the configuration for decreasing a parasitic current can be applied, and effects similar to those according to Embodiment 6 can be acquired.

(137) In Embodiments 1 to 6 described above, while a form in which the contact face 11 is a flat face has been illustrated, the tactile presentation device may employ a form in which the contact face 11 is a curved face. In addition, in Embodiments 1 to 6, while a form in which the tactile presentation device is a computer such as a smartphone has been illustrated, the tactile presentation device may employ various forms such as a form being built in an automated teller machine (ATM) and the like. Furthermore, in Embodiments 1 to 6, while a form in which the tactile presentation device includes the display panel 36 has been illustrated, the tactile presentation device may employ a form not including the display panel 36.

(138) According to the present disclosure, a tactile presentation device has superior effects such as being capable of simultaneously performing the presentation of a tactile sense and the detection of a contact position and not causing interrupt of a tactile sense felt by a user during the use of the tactile presentation device.

(139) It is to be noted that, as used herein and in the appended claims, the singular forms “a”, “an”, and “the” include plural referents unless the context clearly dictates otherwise.

(140) It is to be noted that the disclosed embodiment is illustrative and not restrictive in all aspects. The scope of the present invention is defined by the appended claims rather than by the description preceding them, and all changes that fall within metes and bounds of the claims, or equivalence of such metes and bounds thereof are therefore intended to be embraced by the claims.

Claims

1. A tactile presentation device comprising: a contact face; and a plurality of electrodes arranged in parallel, wherein at least one of the plurality of the electrodes is used for detecting a contact or approach of an object toward the contact face and for presenting a tactile sense to the contact face, a first voltage signal for detecting a contact or approach of an object toward the contact face is applied one after another to the electrodes not adjacent to each other according to elapse of time, a time interval for changing the electrode that the first voltage signal is applied to is shorter than 10 ms, and a second voltage signal for presenting a tactile sense to the contact face is applied continuously to the electrode for which applying of the first voltage signal is finished.
2. The tactile presentation device according to claim 1, wherein the plurality of the electrodes include: a plurality of X electrodes arranged in parallel, and a plurality of Y electrodes arranged in parallel to intersect the X electrodes.
3. A tactile presentation device comprising: a contact face; and a plurality of electrodes arranged in parallel, wherein at least one of the plurality of the electrodes is used for detecting a contact or approach of an object toward the contact face and for presenting a tactile sense to the contact face, a position of the electrode applied a first voltage signal for detecting a contact or approach of an

object toward the contact face is changed discretely according to elapse of time in order to scan the contact face, a time interval for changing the electrode that-applied the first voltage signal is applied to is shorter than 10 ms, and a second voltage signal for presenting a tactile sense to the contact face is applied continuously to the electrode for which applying of the first voltage signal is finished.

4. The tactile presentation device according to claim 2, wherein the plurality of the electrodes include: a plurality of X electrodes arranged in parallel, and a plurality of Y electrodes arranged in parallel to intersect the X electrodes.
