

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250278336

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

SRIVASTAVA; Prakhar et al.

MECHANISM TO ENHANCE LINK BANDWIDTH IN INTERCONNECTS

Abstract

An integrated circuit (IC) device, implemented using chiplets mounted on a substrate, may include a controller and a first plurality of link modules. The first plurality of link modules may be configured to provide data lanes in a multimodule data communication link. The controller may be configured to retrain a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data, reconfigure the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules, and reconfigure the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained.

Inventors: SRIVASTAVA; Prakhar (Lucknow, IN), AKAVARAM; Santhosh Reddy (Hyderabad, IN), BHARATH SAI VARMA; Chintalapati (Hyderabad, IN), SEPURI; Ravi Kumar (Hyderabad, IN), KUMARI; Khushboo (Noida, IN)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 96881441

Appl. No.: 18/594913

Filed: March 04, 2024

Publication Classification

Int. Cl.: G06F11/14 (20060101)

U.S. Cl.:

CPC G06F11/1402 (20130101); G06F2201/86 (20130101)

Background/Summary

TECHNICAL FIELD

[0001] The present disclosure relates generally to integrated circuit technology and, more particularly to optimizing interconnects between chiplets.

BACKGROUND

[0002] Mobile communication devices typically include a variety of components such as circuit boards, integrated circuit (IC) devices, application-specific integrated circuit (ASIC) devices and/or System-on-Chip (SoC) devices. The types of components may include processing circuits, user interface components, storage and other peripheral components that communicate over a serial bus. State-of-the-art mobile application devices demand a small form factor, low cost, a tight power budget, and high electrical performance. For example, wearable processing and communication devices require SoCs and other IC devices that offer higher performance with reduced power requirements in smaller form-factors. Mobile package design has evolved to meet these divergent goals for enabling mobile applications that support multimedia enhancements.

[0003] Chiplet technology can be used to address some of the performance, power, size and other design requirements. Chiplets are a product of improved semi-conductor processing and logic design and can provide an increase in the quantity of logic circuits that can be included in integrated circuit devices. A processing system can be separated into subsystems that may be implemented as individual chiplets. An SoC can be optimized or customized by assembling a subset of available chiplets. The assembled chiplets may communicate with each other via one or more intra-chip data buses or similar data communication interconnects. A mobile application device may include multiple SoCs that communicate with each other via similar inter-chip interconnects.

[0004] Interconnects between chiplets can be implemented using some combination of point-to-point interfaces and multi-drop buses. Interconnect architectures may be based on a variety of technologies, including Peripheral Component Interconnect Express (PCIe), Universal Serial Bus, and others. Ever-increasing bandwidth and data throughput requirements have necessitated the development of more complex interconnect architectures that require calibration and training to ensure link reliability and integrity.

[0005] There is an ongoing need to improve availability, training and repair techniques for interconnections used to couple chiplets in SoCs.

SUMMARY

[0006] Certain aspects of the disclosure relate to IC devices that include multiple chiplets and to retraining techniques that optimize availability of an interconnection between chiplets after a fault is detected in one or more link modules.

[0007] In various aspects of the disclosure, a method for operating an interconnection between chiplets includes transmitting or receiving data over a multimodule data communication link that uses a first plurality of link modules to provide data transmit lanes and data receive lanes, retraining a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data, reconfiguring the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules, and reconfiguring the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained.

[0008] In various aspects of the disclosure, a processor-readable storage medium stores code that, when executed by a processor causes a processing circuit to transmit or receive data over a

multimodule data communication link that uses a first plurality of link modules to provide data transmit lanes and data receive lanes, retrain a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data, reconfigure the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules, and reconfigure the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained.

[0009] In various aspects of the disclosure, a communication interface in a chiplet includes a first plurality of link modules configured to provide data transmit lanes and data receive lanes in a multimodule data communication link, and a controller. The controller may be configured retrain a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data, reconfigure the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules, and reconfigure the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained.

[0010] In certain aspects, the first plurality of link modules includes a first number of link modules that is defined by Universal Chiplet Interconnect Express (UCIe) specifications and the second plurality of link modules includes a second number of link modules that is defined by the UCIe specifications.

[0011] In certain aspects, the second plurality of link modules excludes at least one link module in the first plurality of link modules that is active and available for transmitting or receiving the data.

[0012] In certain aspects, the second plurality of link modules includes a quantity of link modules that is defined based on number of the other link modules in the first plurality of link modules that are active and available for transmitting or receiving data. The number of data transmit lanes and data receive lanes provided by each link module may be defined by UCIe specifications. In one example, each link module can be configured to provide 64 data transmit lanes and 64 data receive lanes in accordance with an advanced packaging option defined by the UCIe specifications. In another example, each link module can be configured to provide 16 data transmit lanes and 16 data receive lanes in accordance with a standard packaging option defined by the UCIe specifications.

[0013] In certain aspects, each link module in the first plurality of link modules may be caused to enter a link initialization state after the failed link module has been successfully retrained. Each link module in the first plurality of link modules may be bound to the multimodule data communication link in a corresponding link initialization state. A sideband link in one of the first plurality of link modules may be designated to transmit and receive link status and control messages for all bound link modules in the first plurality of link modules. A sideband link in one of the second plurality of link modules may be designated to transmit and receive link status and control messages for all bound link modules in the second plurality of link modules. Each link module in the first plurality of link modules may be bound to the multimodule data communication link in accordance with UCIe specifications. The failed link module may be retrained in accordance with UCIe specifications.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0014] FIG. 1 illustrates an apparatus employing interconnected chiplets.

[0015] FIG. 2 illustrates certain aspects of an SoC constructed from chiplets.

[0016] FIG. 3 illustrates an example of an SoC in which chiplets are stacked vertically on a substrate.

[0017] FIG. 4 illustrates an example of advanced packaging option implemented between a first die and a second die.

[0018] FIG. 5 illustrates an example of data transmission through an advanced packaging option interface configured to operate in accordance with Universal Chiplet Interconnect Express (UCIe) specifications.

[0019] FIG. 6 illustrates an initialization procedure defined by UCIe specifications.

[0020] FIG. 7 illustrates inter-die communication links configured in accordance with UCIe specifications.

[0021] FIG. 8 illustrates an example of mainband training within the mainband training state illustrated in FIG. 6.

[0022] FIG. 9 is a decision flow chart that illustrates certain decision points and transitions encountered in mainband training.

[0023] FIG. 10 illustrates certain aspects of link error handling in a multimodule link that uses four link modules to provide data lanes.

[0024] FIG. 11 is a state diagram that illustrates certain aspects of retraining defined by UCIe specifications for a multimodule link.

[0025] FIG. 12 is a diagram that illustrates the effect on multimodule link availability for inter-chiplet communication.

[0026] FIG. 13 illustrates certain aspects of a link error handling scheme for a multimodule inter-die communication link that may be implemented in accordance with certain aspects of this disclosure.

[0027] FIG. 14 illustrates certain aspects of a link error handling scheme for a multimodule inter-die communication link that may be implemented in accordance with certain aspects of this disclosure.

[0028] FIG. 15 illustrates effects on availability of an inter-chiplet communication using a link error handling scheme implemented in accordance with certain aspects of this disclosure.

[0029] FIG. 16 is a flowchart of a method for operating an interconnection between chiplets in accordance with certain aspects of this disclosure.

DETAILED DESCRIPTION

[0030] The detailed description set forth below in connection with the appended drawings is intended as a description of various configurations and is not intended to represent the only configurations in which the concepts described herein may be practiced. The detailed description includes specific details for the purpose of providing a thorough understanding of various concepts. However, it will be apparent to those skilled in the art that these concepts may be practiced without these specific details. In some instances, well-known structures and components are shown in block diagram form in order to avoid obscuring such concepts.

[0031] Several aspects of the invention will now be presented with reference to various apparatus and methods. These apparatus and methods will be described in the following detailed description and illustrated in the accompanying drawings by various blocks, modules, components, circuits, steps, processes, algorithms, etc. (collectively referred to as “elements”). These elements may be implemented using electronic hardware, computer software, or any combination thereof. Whether such elements are implemented as hardware or software depends upon the particular application and design constraints imposed on the overall system.

[0032] Data communication links employed by SoCs and other IC devices to connect processors with modems and other peripherals may be operated in accordance with industry or proprietary standards or protocols associated with certain functions or types of devices. In one example, the peripheral component interconnect express (PCIe) standard is a high-speed interface that enables transmission over a high-speed link at data rates measured in gigabits per second. A high-speed

interface operated in accordance with PCIe standards and protocols has multiple standby modes when the link is inactive. In operation, one device acts as a host that can communicate through PCIe links with multiple devices, which may be referred to as endpoints. In a PCIe link, data is transmitted in differential signals over one or more two-line lanes. Lanes may provide duplex, serial point-to-point connections.

[0033] Serial data links may be used to interconnect certain electronic devices that are subcomponents of an apparatus such as a cellular phone, a smart phone, a session initiation protocol (SIP) phone, a laptop, a notebook, a netbook, a smartbook, a personal digital assistant (PDA), a satellite radio, a global positioning system (GPS) device, a smart home device, intelligent lighting, a multimedia device, a video device, a digital audio player (e.g., MP3 player), a camera, a game console, an entertainment device, a vehicle component, a wearable computing device (e.g., a smart watch, a health or fitness tracker, eyewear, etc.), an appliance, a sensor, a security device, a vending machine, a smart meter, or any other similar functioning device.

[0034] FIG. 1 illustrates an example of an apparatus **100** that may be implemented using multiple chiplets coupled through one or more data communication buses. The apparatus may be enclosed within a wearable device, such as the illustrated smartwatch **130**. A processing circuit **102** of the apparatus **100** includes multiple circuits or devices **104**, **106** and/or **108**. In various examples, the processing circuit **102** is implemented using one or more ASICS, chiplets, an SoC or other devices arranged in a configuration that can be adapted for use in mobile computing, embedded computing, edge computing. In one example, the apparatus **100** may be configured to support multiple communication technologies, modes or protocols and the processing circuit **102** includes a combination of devices including an SoC **104**, one or more peripheral devices **106**, and a transceiver **108** that cooperate to enable the apparatus to communicate through an antenna **122** with a radio access network, a core access network, the Internet and/or another network.

[0035] The SoC **104** may include one or more processors **112**, one or more modems **110**, on-board memory **114**, a bus interface circuit **116** and/or other logic circuits or functions. The processing circuit **102** may be controlled by an operating system that provides an application programming interface (API) layer that enables the one or more processors **112** to execute software modules residing in the on-board memory **114** or other processor-readable storage **118** provided on the processing circuit **102**. The software modules may include instructions and data stored in the on-board memory **114** or processor-readable storage **118**. The SoC **104** may access its on-board memory **114**, the processor-readable storage **118**, and/or storage external to the processing circuit **102**. The on-board memory **114**, the processor-readable storage **118** may include read-only memory (ROM) or random-access memory (RAM), electrically erasable programmable ROM (EEPROM), flash cards, or any memory device that can be used in processing systems and computing platforms. The processing circuit **102** may include, implement, or have access to a local database or other parameter storage that can maintain operational parameters and other information used to configure and operate the apparatus **100** and/or the processing circuit **102**. The local database may be implemented using registers, a database module, flash memory, magnetic media, EEPROM, soft or hard disk, or the like. The processing circuit **102** may also be operably coupled to external devices such as the antenna **122**, a display **134**, operator controls **132**, switches or buttons, among other components. A user interface module may be configured to manage the display **134**, operator controls **132**, etc. and may communicate with other elements of the processing circuit **102** through one or more serial data interconnects.

[0036] The processing circuit **102** may provide multiple buses **120** that enable communication between two or more devices **104**, **106**, and/or **108**. In one example, the SoC **104** may include bus interface circuits **116** coupled to one or more of the buses **120**. Each of the bus interface circuits **116** may include a combination of circuits, counters, timers, control logic and other configurable circuits or modules. In one example, certain bus interface circuits **116** may be configured to operate in accordance with standards-defined communication specifications or protocols. The processing

circuit **102** may include or control a power management function that configures and manages the operation of the apparatus **100**.

[0037] The illustrated smartwatch **130**, other portable or wearable processing and/or communication devices (referred to collectively as portable communication devices or PCDs), sensors, instruments, appliances and other such devices include one or more ICs. These devices may include mobile phones, tablet computers, palmtop computers, portable digital assistants (PDAs), portable game consoles, and other portable electronic devices. PCDs commonly contain integrated circuits or SoCs that include numerous components or subsystems designed to work together to deliver functionality to a user. The various SoC subsystems may communicate with each other via one or more intra-chip data buses or similar data communication interconnects. PCDs may have multiple SoCs that communicate with each other via similar inter-chip interconnects. The ICs are typically packaged in an IC package, which may be referred to as a “semiconductor package” or “chip package.” The IC package typically includes a package substrate and one or more IC chips or other electronic modules mounted to the package substrate to provide electrical connectivity to the IC chips. For example, an IC chip in an IC package may be configured as an SoC. The IC chips are electrically coupled to other IC chips and/or to other components in the IC package through electrical coupling to metal lines in the package substrate. The IC chips can also be electrically coupled to other circuits outside the IC package through electrical connections of external metal interconnects (e.g., solder bumps) of the IC package.

[0038] Process technology employed to manufacture semiconductor devices, including IC devices is continually improving. Process technology includes the manufacturing methods used to make IC devices and defines transistor size, operating voltages and switching speeds. Features that are constituent elements of circuits in an IC device may be referred as technology nodes and/or process nodes. The terms technology node, process node, process technology may be used to characterize a specific semiconductor manufacturing process and corresponding design rules. Faster and more power-efficient technology nodes are being continuously developed through the use of smaller feature size to produce smaller transistors that enable the manufacture of higher-density ICs. Design rules for newer process technology that use low-voltage transistors may preclude the use of higher voltage transistors supported by previous process technology generations. The unavailability of certain higher-voltage transistors may present an impediment to circuit designers for IC devices that include multiple voltage domains.

[0039] The increasing complexity and functionality required from semiconductor devices tends to increase the physical dimensions of integrated circuit devices in which they are embodied. An upper limit on integrated circuit device is the maximum “reticle” size that in some instances refers to the size of the photomask used to manufacture the integrated circuit devices. Chiplets provide one approach to avoiding the maximum reticle size. Moreover, chiplet technology can be used to address some of the performance, power and size design requirements for complex SoCs, including SoCs used in certain mobile or wearable devices. The use of smaller dies can improve manufacturing yields.

[0040] The block diagram in FIG. 2 illustrates certain aspects of an SoC **200** that can be constructed using chiplets. The SoC **200** may be configured by selecting a combination of chiplets that implement certain subsystems or distinct functional elements. In the illustrated example, the SoC **200** includes a set of primary chiplets **202** that enable the SoC **200** to perform core processing, security and communication functions. The set of primary chiplets **202** include a processor, memory and one or more modems. The illustrated SoC **200** also includes a set of application-specific chiplets **204** that includes an application processor, display driver, camera interface and audio controller. In a remote sensing device or appliance, the audio-visual components could be omitted and may be replaced with analog-to-digital controllers, for example.

[0041] The SoC **200** may include a variety of processing engines, such as central processing units (CPUs) with multiple cores, graphical processing units (GPUs), digital signal processors (DSPs),

neural processing units (NPUs), wireless transceiver units (also referred to as modems), peripherals, display and imaging interfaces, etc. Each of these subsystems and other functional elements can be implemented as an individual chiplet, or as a combination of chiplets. The chiplets included in the SoC **200** can be proprietary or may be acquired from a variety of sources. An SoC may be constructed from chiplets manufactured at different process nodes and/or operated at different voltages. FIG. 3 illustrates an example of an SoC **300** in which certain chiplets **304**, **306**, **308** are stacked vertically on a substrate **310**. Some chiplets can be included in stacks that are deployed across the surface of the substrate **310**, while other chiplets may be individually mounted on the surface of the substrate. Chiplets may be mounted on the surface of the substrate using solder balls **302** that provide electrical and/or thermal coupling between substrate and the mounted chiplets. An interconnect structure may be formed that enables chiplets **304**, **306**, **308** in a stack of chiplets to communicate with one another, with other chiplets mounted on the substrate **310** and with input/output structures that connect the SoC **200** with other circuits, displays, imaging sensors and other peripherals with an apparatus.

[0042] The use of chiplets can reduce the areal size of the substrate **310** and increase three-dimensional packing density. The constituent chiplets may provide complex features and high performance within a smaller form-factor operated at lower power specifications. Moreover, each chiplet may define multiple power domains, operate at different frequencies and different chiplets may manage power/frequency modes independently and. In some instances, two or more chiplets may be operated in mutually exclusive power states. Additionally, operating conditions for an SoC depend on the type, number and arrangement of chiplets included on the substrate in addition to the modes of operation defined by applications. It is necessary to consider power usage by all chiplets in the SoC in order to ensure compliance with power budgets assigned for an application or device.

[0043] Conventional chiplet-based implementations suffer from limitations that include complex or difficult interconnect routing, local hotspots arising from routing congestion caused by connection architecture and challenges to signal timing specifications. In certain examples, local hotspots can arise from routing congestion, increased feature complexity and circuit concentrations. In certain examples, signal timing specifications can be compromised due to the necessity for an increased number of isolation clamps due to logic placement, number of voltage domains and reduced floorplan. Long wire crossings between chiplets can cause routing congestion and lossy interconnects.

[0044] Each chiplet in an SoC may be included to perform a specific function or type of function and the configuration of the chiplets can introduce further complexities and challenges for designers. For example, one chiplet may include radio frequency front end circuits that produce high frequency signals ranging up to 5 GHz or more, and may further include interfaces that are used by low-frequency power management circuits. A designer may import previously defined circuit blocks to implement some of the internal functions. These circuit blocks may be referred to as macros. Imported circuit blocks for a given process technology may be described, characterized or defined by a set of masks, hardware description language, specifications and test data.

Commercially available or proprietary circuit blocks may be referred to as hard macros. Hard macros are tested and verified for a set of design and operating specifications. It is common for hard macros and other circuit blocks to define multiple power domains.

[0045] The Universal Chiplet Interconnect Express (UCIe) is an example of a standardized chiplet interconnect specification. The UCIe specification enables construction of large System-on-Chip (SoC) packages that in aggregate can exceed the maximum reticle size. The adoption of the UCIe specification has facilitated the integration of chiplets manufactured by different vendors into a single package. The UCIe specification enables the integration of chiplets fabricated using different silicon manufacturing processes into a single package, as required or desired for a specific device type, computing performance and/or to better meet power consumption budgets. The UCIe specification defines physical layer circuits and interconnects, protocol stacks and defines a

software architecture and procedures to be used for compliance testing.

[0046] The UCIe specification defines different packaging options. One packaging option is the standard packaging option, which may also be referred to as the two-dimensional (2D) option. The standard packaging option may be applied to technology that can be used for low-cost devices and long-reach channels, where distances of between 10 mm and 25 mm may be considered to be long-reach. Another packaging option is the advanced packaging option, which may also be referred to as the 2.5D option. The advanced packaging option may be applied to technology that can be used for performance-optimized applications with short channel lengths. For example, channels that have a length that is less than 2 mm may be considered to be a short channel.

[0047] FIG. 4 illustrates an example of advanced packaging option link module **400** implemented between a first die **402** and a second die **404**. The link module **400** provides an interface that supports separate high-speed communication and low-speed communication interfaces. A main communication link (the mainband link **406**) provides the primary communication path and is used to exchange application data and messages. A secondary communication link (the sideband link **408**) provides a communication path for control data, including link state and status messages, power management messages, error handling handshake messages, and messages related to transition negotiation regarding operational state of the first die **402** and a second die **404**.

[0048] In the illustrated example, the mainband transmitter physical layer (PHY) circuit **412** in the first die **402** is coupled to a mainband data bus **432a** over which up to 64-bit parallel data can be transmitted according to timing provided by one or more of two mainband clock signals transmitted over mainband clock lines **432b**. The mainband data bus **432a** and mainband clock lines **432b** are driven by the mainband transmitter PHY circuit **412**. The mainband transmitter PHY circuit **412** in the first die **402** may transmit a framing signal over a mainband valid line **436a** to indicate framing information associated with transmitted data and a track signal over a track line **436b** to enable the receiver to correct or adjust phase in received versions of the two mainband clock signals. The mainband transmitter PHY circuit **412** is coupled to six redundant pins of the first die **402**. The redundant pins may be used to replace data or clock lines that do not function according to specification due to manufacturing process variances or low-quality results from a packaging process. The redundant pins can reduce yield loss.

[0049] The UCIe specification defines test and repair procedures that are based on the available redundant pins. One redundant pin is allocated for use as a redundant mainband clock line **434a**, four redundant pins are allocated for transmission data over redundant mainband data lines **434b** and one redundant pin is allocated for a redundant valid line **438**.

[0050] The mainband receiver PHY circuit **416** in the second die **404** is coupled to the mainband data bus **432a** over which it can receive up to 64-bit parallel data according to timing provided by one or more of two mainband clock signals received over the mainband clock lines **432b**. The mainband clock signals are provided by the mainband transmitter PHY circuit **412** in the first die **402**. The mainband receiver PHY circuit **416** in the second die **404** may receive a mainband valid signal over a mainband valid line **436a** to indicate framing information associated with transmitted data and a track signal from the track line **436b** to enable correction or adjustment of phase in the two mainband clock signals. The mainband receiver PHY circuit **416** is further coupled to six redundant pins of the second die **404**. One redundant pin may be allocated as the redundant mainband clock line **434a**, four redundant pins are allocated as the redundant mainband data lines **434b** and one redundant pin is allocated as a redundant valid line **438**.

[0051] The mainband transmitter PHY circuit **418** in the second die **404** is coupled to a primary mainband data bus **442a** over which it can transmit up to 64-bit parallel data according to timing provided by one or more of two clock signals transmitted over clock lines **442b** by the mainband transmitter PHY circuit **418**. The mainband transmitter PHY circuit **418** in the second die **404** may transmit a mainband valid signal over the mainband valid line **446a** to indicate framing information associated with transmitted data and a track signal over the track line **446b** to enable the receiver to

correct or adjust phase in received versions of the two clock signals transmitted over the clock lines **442b**. The mainband transmitter PHY circuit **412** is coupled to a further six redundant pins of the second die **404**. These redundant pins may be used to replace data or clock lines that do not function according to specification due to manufacturing process variances or low-quality results from a packaging process. The redundant pins can reduce yield loss. One redundant pin is allocated for use as a redundant mainband clock line **444a**, four redundant pins are allocated for transmission of redundant mainband data lines **444b** and one redundant pin is allocated for use as a redundant valid line **448**.

[0052] The mainband receiver PHY circuit **414** in the first die **402** is coupled to the primary mainband data bus **442a** over which it can receive up to 64-bit parallel data according to timing provided by one or more of the two mainband clock signals received over the mainband clock lines **432b** from the mainband transmitter PHY circuit **418** in the second die **404**. The mainband receiver PHY circuit **414** in the first die **402** may receive a mainband valid signal over the mainband valid line **446a** that indicates framing information associated with transmitted data and a track signal over the track line **446b** to enable correction or adjustment of phase in the two mainband clock signals received over the mainband clock lines **432b**. The mainband receiver PHY circuit **414** is further coupled to a further six redundant pins of the first die **402**. One redundant pin may be allocated for receiving the redundant mainband clock line **444a**, four redundant pins are allocated for receiving the redundant mainband data lines **444b** and one redundant pin is allocated for receiving a framing signal over the redundant valid line **448**.

[0053] In the illustrated example, the sideband transmitter PHY circuit **422** in the first die **402** is coupled to a sideband data line **452a** over which it can transmit data according to timing provided by a sideband clock signal that is transmitted over a sideband clock line **452b** by the sideband transmitter PHY circuit **422**. The sideband transmitter PHY circuit **422** in the first die **402** may be configured to transmit over a redundant sideband data line **454a** and a redundant sideband clock line **454b**. The sideband receiver PHY circuit **426** in the second die **404** is coupled to the sideband data line **452a** over which it can receive data according to timing in the sideband clock signal transmitted over the sideband clock line **452b** by the sideband transmitter PHY circuit **422** in the first die **402**. The sideband receiver PHY circuit **426** in the second die **404** may be configured to receive signals over the redundant sideband data line **454a** and the redundant sideband clock line **454b**. The sideband transmitter PHY circuit **428** in the second die **404** is coupled to a sideband data line **462a** over which it can transmit data according to timing provided by a sideband clock signal transmitted over the sideband clock line **462b**. The sideband transmitter PHY circuit **428** in the second die **404** may transmit a redundant sideband data signal over a redundant sideband data line **464a** and a redundant sideband clock signal over a redundant sideband clock line **464b**. The sideband receiver PHY circuit **424** in the first die **402** is coupled to the sideband data line **462a** over which it can receive data according to timing in the sideband clock signal received over the sideband clock line **462b** and provided by the sideband transmitter PHY circuit **428** in the second die **404**. The sideband receiver PHY circuit **424** in the first die **402** may receive redundant sideband data over a redundant sideband data line **464a** and the redundant sideband clock signal over the redundant sideband clock line **464b**.

[0054] FIG. 5 illustrates an example of data transmission through an advanced packaging option interface **500** configured to operate in accordance with UCIe specifications. Certain elements of the circuits illustrated in FIG. 5 are abstracted or summarized. For example, FIG. 5 depicts one data or data valid lane **532** that couples the first die **402** and the second die **404**. Multiple data or data valid lanes are typically used. The first die **402** includes a serializer **502** that is configured to receive parallel input data **510**. The data stream produced by the serializer **502** is provided to a data line driving circuit **504** that transmits the datastream over the data or data valid lane **532**. A data receiving circuit **506** coupled to the data or data valid lane **532** cooperates with a deserializer **508** to sample or capture bits in the received bitstream and provide parallel output data **520**.

[0055] A clock generator **512** generates one or more clock signals that can be used to serialize the parallel input data **510** and to control data transmission over the data or data valid lane **532**. The clock generator **512** provides a first clock signal **530** that is used to control timing of the serializer **502**. In certain implementations, data is encoded in a double data rate signal in which each two bits of data are transmitted for each cycle of a transmitted clock signal. For example, the data or data valid lane **532** may be configured for a 16 gigabits per second (Gbps) data rate when the first clock signal **530** has a frequency of 8 GHz. The first clock signal **530** may be coupled to the serializer **502** through a duty cycle correction circuit **522** to ensure that the durations of both half-cycles of the first clock signal **530** are closely matched. The clock generator **512** may provide a second clock signal **540** to a clock line driving circuit **514** that drives the clock lane **534**. The second clock signal **540** may be coupled to the clock line driving circuit **514** through a duty cycle correction circuit **518**. The output of the duty cycle correction circuit **518** may be provided to a tracking line driving circuit **524**, which transmits a version of the clock signal over the track lane **536**.

[0056] At the receiver, a clock receiving circuit **516** coupled to the clock lane **534** and a track receiving circuit **526** coupled to the track lane **536** provide versions **544**, **546** of the second clock signal **540** to a phase correction or alignment circuit **528** that produces a clock signal **548** that is used to clock the deserializer **508**.

[0057] The example illustrated in FIG. 5 relates to mainband communication in which a framing signal (i.e. a data valid signal) is transmitted over a data or data valid lane **532** and a tracking signal is transmitted over a track lane **536**. The circuits and structures illustrated in FIG. 5 correspond in some respects to the sideband communication used to exchange command and control information. Furthermore, the example illustrated in FIG. 5 shows communication from the first die **402** to the second die **404**. Similar circuits and structures may be configured to enable mainband or sideband communication from the second die **404** to the first die **402**.

[0058] An initialization procedure provided by the UCIe specification enables the first die **402** and the second die **404** to establish reliable connections. The initialization procedure defines states that correspond to different phases of link initialization. The participants in the initialization procedure are required to progress through a sequence of states before the link can be declared to be active. The initialization procedure may be managed or controlled in each die by a finite state machine (FSM) or by another controller or processor. In the illustrated example, the FSM **552** in the first die **402** and the FSM **562** in the second die **404** may be configured to operate as link training and status state machines (LTSSMs) in accordance with UCIe specifications. Each of the FSMs **552**, **562** may be coupled to one or more control registers **554**, **564** that maintain state, configuration and other control information that can be used to control state transitions.

[0059] FIG. 6 is a state diagram **600** that illustrates an initialization procedure defined by UCIe specifications. The initialization procedure may be managed or controlled using a processor, microcontroller or an FSM **552**, **562** configured to implement an LTSSM in accordance with UCIe specifications. The LTSSM may be initially in a reset state **602** before entering the sideband initialization state **604**. The reset state **602** may be entered following a system reset or after detecting an error during operation, including link training operations. The sideband initialization state **604** is used to establish reliable control and command communications over the lower-frequency sideband link. The participants in the initialization procedure are required to test all combinations of lines that include a data line and a clock line. In one example, the combinations tested include: the sideband data line **452a** and the sideband clock line **452b**; the redundant sideband data line **454a** and the redundant sideband clock line **454b**; the sideband data line **452a** and the redundant sideband clock line **454b**; and the redundant sideband data line **454a** and sideband clock line **452b**. If, during testing, data transmission is unsuccessful using the sideband data line **452a** and sideband clock line **452b**, then the link may be established using another combination of clock and data lines.

[0060] Sideband initialization testing may include transmission and detection of one or more

training patterns. In one example, a training pattern may include a transmission of data in 64 data bit transmission intervals and driving data lines low for 32 data bit transmission intervals. Data bit transmission intervals may correspond to one clock cycle and may be referred to as unit intervals (UIs). The duration of a UI defines the minimum time between transitions in signaling state of a data signal. The training patterns are conventionally transmitted over all combinations of the redundant lines. For example, the sideband transmitter PHY circuit **422** transmits the training pattern over all possible clock-plus-data combinations of the sideband data line **452a**, sideband clock line **452b**, the redundant sideband data line **454a** and the redundant sideband clock line **454b**. [0061] When the sideband link has been initiated and is functional, the initialization procedure proceeds to a mainband initialization state **606**. In certain implementations, each of the participants in the initialization procedure may test the combination of the mainband data bus **432a**, the mainband valid line **436a**, the track line **436b** and one or more of the mainband clock lines **432b**. If data transmission is unsuccessful using the mainband data bus **432a**, the mainband valid line **436a**, the track line **436b** and the mainband clock lines **432b**, then the link may be established using the redundant mainband clock line **434a**, one or more of the redundant mainband data lines **434b**, and/or the redundant valid line **438**.

[0062] The participants in the initialization procedure may test the combination of the primary mainband data bus **442a**, mainband valid line **446a**, track line **446b** and primary mainband clock lines **442b**. If data transmission is unsuccessful using the primary mainband data bus **442a**, mainband valid line **446a**, track line **446b** and mainband clock lines **442b**, then the link may be established using the redundant mainband clock line **444a**, one or more of the redundant mainband data lines **444b**, and/or the redundant valid line **448**.

[0063] When the mainband link has been tested and repaired where necessary, the initialization procedure proceeds to a mainband training state **608**. The mainband training state **608** is used to configure and calibrate the PHY circuits **412**, **414**, **416**, **418**. In some implementations, a maximum speed of operation is configured and each transmit/receive pair of PHY circuits **412/416** or **414/418** cooperate to perform die-to-die training. The maximum speed of operation may correspond to a negotiated data rate. In one example, die-to-die training may be performed to center one or more clock signals with respect to data signals. Calibration may include calibrating the clock generator **512**, the duty cycle control circuits **518**, **522**, line driving circuits **504**, **514**, **524**, receiving circuits **506**, **516**, **526** and phase correction or alignment circuit **528**. In one example, the clock generator **512** may be calibrated to tune the frequency of the clock signals **530**, **540**. In another example, the duty cycle control circuits **518**, **522** may be calibrated to optimize timing of the clock signals provided to the serializer **502** and line driving circuits **514**, **524**. In another example, equalizers in the line driving circuits **504**, **514**, **524** and receiving circuits **506**, **516**, **526** may be calibrated to accommodate or compensate for transmission errors.

[0064] A failure to successfully complete initialization or training in any of the bring-up states **604**, **606**, **608**, **610** causes the participants in the initialization procedure to enter a training error state **614** which ultimately results in reentry to the reset state **602**.

[0065] When the mainband link has been trained, then the link may be initialized in the link initialization state **610**. In the link initialization state **610**, messages are exchanged between the two dies **402**, **404**, using the sideband link **408**. In one example, link initialization includes establishing initial communication state, clearing buffers and initializing protocol stacks. When the link is initialized, the active state **620** is entered. In some instances, the communication link may be idled and/or caused to enter a low-power state **612**. The low-power state **612** may support multiple levels of low-power operation. For example, an L1 power-down mode may maintain certain subcircuits in the PHY circuits **412**, **414**, **416**, **418** in an active, reduced voltage state, while an L2 power-down mode may power down subcircuits in the PHY circuits **412**, **414**, **416**, **418** that are required to maintain calibration of the link. The low-power state **612** is typically entered from the active state **620**. Exit from the L1 power-down mode may cause a transition to the mainband training state **608**.

in order to reconfigure or recalibrate the PHY circuits **412**, **414**, **416**, **418**. Exit from the L2 power-down mode may cause a transition to the reset state **602**.

[0066] Either device coupled to the communication link may cause entry to a PHY retraining state **616**. The PHY retraining state **616** may be entered when an error is detected in data transmissions over the mainband data bus **432a**. The initialization procedure may be re-entered through the mainband training state **608** in order to reconfigure or recalibrate the PHY circuits **412**, **414**, **416**, **418**.

[0067] Conventional UCIe initialization procedures require testing of all combinations of the sideband data line **452a**, sideband clock line **452b**, the redundant sideband data line **454a** and the redundant sideband clock line **454b** by transmitting and detecting a prolonged training pattern for each combination. The PHY circuit **426** samples and validates a training pattern received over the first sideband data line **452a** using the clock signal received over the first sideband clock line **452b** and also samples and validates a training pattern received by the first sideband data line **452a** using the clock signal received over the second sideband clock line **454b**. Additionally, the PHY circuit **426** samples and validates a training pattern received by the second sideband data line **454a** using the clock signal received over the first sideband clock line **452b** and also samples and validates a training pattern received by the second sideband data line **454a** using the clock signal received over the second sideband clock line **454b**. The PHY circuit **424** samples and validates a training pattern received by the third sideband data line **462a** using the clock signal received over the third sideband clock line **462b** and also samples and validates a training pattern received by the third sideband data line **462a** using the clock signal received over the fourth sideband clock line **464b**. Additionally, the PHY circuit **424** samples and validates a training pattern received by the fourth sideband data line **464a** using the clock signal received over the third sideband clock line **462b** and also samples and validates a training pattern received by the fourth sideband data line **464a** using the clock signal received over the fourth sideband clock line **464b**. It will be appreciated that a minimum of 8 training patterns are required to test all combinations of clock and data lines for both directions of transmission in the sideband link.

[0068] In some systems, it may be necessary or desirable to provide data communication links that exceed 64 read lines and/or 64 write lines. Certain UCIe specifications define a multi-module PHY logic (MMPL) architecture and associated procedures that provide inter-die communication links built on multiple link modules **400**. The link modules **400** are initialized and trained independently. The mainband training state **608** (see FIG. 6) is configured to wait for completion of training procedures for all configured link modules **400** before the configured link modules are bound according to MMPL specifications during the link initialization state **610**. Binding link modules **400** may include combining the data lanes and associated control signals into a block of data lanes from which individual data lanes or groups of data lanes may be assigned for usage defined by an application. Binding link modules **400** may further include assigning one sideband link to transmit and receive communication link status and control messages for all bound link modules **400**.

[0069] In the example illustrated in FIG. 4, each link module **400** includes a mainband link **406** that provides a bidirectional mainband data width of 64 bits with associated clock, valid and track signals. Each link module **400** includes a physical sideband link **408** configured as illustrated in FIG. 4. According to UCIe specifications for MMPL, one logical sideband link is defined for bound link modules **400** and is used to carry all die-to-die sideband messages. The logical sideband link is typically mapped to the physical sideband link **408** in the link module **400** that provides the least significant bit data lane. Link modules **400** that are bound according to UCIe specifications for MMPL may be assigned logical numbers, with Module-0 providing the least significant bit data lane.

[0070] FIG. 7 illustrates examples of inter-die communication links **700**, **710**, **720** configured in accordance with UCIe specifications. The first inter-die communication link **700** features a single link module **702** that corresponds in many respects to the link module **400** illustrated in FIG. 4. The

link module **702** includes multiple layers of hardware and software modules, including a die-to-die adaption layer **704** that may be configured to manage inter-die communication, physical layer (PHY) logic **706** that controls and manages the electrical characteristics of analog front-end circuits and the configuration of logic circuits used to transmit or receive over the mainband link **708a** and/or the sideband link **708b**. The first inter-die communication link **700** provides a nominal 64-bit mainband data path in both transmit and receive directions. The second inter-die communication link **710** includes two link modules **712**, **714**, each of which correspond to the link module **702** and/or to the link module **400** illustrated in FIG. **4**. The second inter-die communication link **710** provides a nominal 128-bit mainband data path in both transmit and receive directions. The third inter-die communication link **720** includes four link modules **722**, **724**, **726**, **728**, each of which correspond to the link module **702** and/or to the link module **400** illustrated in FIG. **4**. The second inter-die communication link **720** provides a nominal 256-bit mainband data path in both transmit and receive directions. It can be expected that certain applications or systems may not transmit or receive over every mainband data line provided by an inter-die communication link **700**, **710**, **720**. In systems that are configured to bind two link modules **712**, **714**, four link modules **722**, **724**, **726**, **728** or any other number of link modules, each link module **712**, **714**, **722**, **724**, **726**, **728** is initialized and trained independently. In some implementations, the final configuration of a multi-module link is determined in the mainband training state **608** (see FIG. **6**) based on the number and identity of link modules **712**, **714**, **722**, **724**, **726**, **728** that have been successfully trained. In the example of the second inter-die communication link **710**, the two link modules **712**, **714** may be bound according to MMPL specifications in the link initialization state **610** when both link modules **712**, **714** have been successfully trained. When a persistent error occurs during training of either link module **712**, **714**, a 64-bit link may be configured using the link module **712**, **714** that was successfully trained.

[0071] In the example of the third inter-die communication link **720**, the four link modules **722**, **724**, **726**, **728** may be bound to provide a 256-bit link according to MMPL specifications during the link initialization state **610** when all link modules **722**, **724**, **726**, **728** have been successfully trained. MMPL specifications provide that a 128-bit link may be configured using two link modules **722**, **724**, **726** and/or **728** that were successfully trained when a persistent error occurs during training of one or two of the link modules **722**, **724**, **726** and/or **728**. MMPL specifications also provide that a 64-bit link can be configured when only one of the link modules **722**, **724**, **726** or **728** is successfully trained.

[0072] FIG. **8** is a state diagram **800** that illustrates an example of mainband training within the mainband training state **608** illustrated in FIG. **6**. A Speed Idle state **802** is entered from a power-down state **612** and/or after circuits associated with data and valid lanes have been configured or trained. The data rate and frequency of associated clock signals may be configured for all link modules in the Speed Idle state **802**. The training procedure then transitions to a transmitter calibration state **804** followed by a receiver calibration state **806** in which each link module calibrates its own physical layer circuits. The receive clock calibration state **808** follows in which edges of one or more clock signals in a receiving link module are calibrated with a clock signal transmitted over a clock lane by a transmitting link module. Timing of sampling signals for data and valid signals may then be performed. The results of the training are assessed in the Link Speed state **810**. When all link modules have been successfully trained, a transition **820** from the mainband training state **608** to the link initialization state **610** may be executed. Certain errors reported during training may be correctable, in which case a transition **822** to a PHY repair state **812** permits a link module to reconfigure its physical circuits and reenter the training procedure, at the receiver calibration state **806** for example. Certain errors reported during training may be persistent or sufficiently serious that link data rate and frequency of associated clock signals may be reconfigured for all link modules. A transition **824** to the Speed Idle state **802** restarts certain aspects of training for all link modules at the newly reconfigured link data rate and clock

frequency. In some instances, a transition **826** to the PHY retraining state **616** may be initiated when failures recur after one or more reconfigurations of link data rate and clock frequency. [0073] FIG. **9** is a decision flow chart **900** that illustrates certain decision points and transitions encountered during mainband training. At block **902**, entry is made to Link Speed state **810** which causes all link modules to be trained according to a defined data rate and frequency of associated clock signals. If at block **904**, the results of training indicate that all link modules have been successfully trained, then the link initialization state **610** may be entered at block **912**. If at block **904**, the results of training indicate that one or more link modules have reported unresolved errors during training, then the decision process proceeds to block **906**.

[0074] At block **906**, it may be determined whether one or more link modules are deemed to be irreparable at the current clock frequency. If at block **906** the results of training indicate that half or more of the modules have been successfully trained, then the decision may be taken to reduce the number of link modules to be configured at block **916** before entering the link initialization state **610** at block **912**. Reducing the number of link modules to be configured in a multimodule link may be referred to herein as downgrading the multimodule link configuration. The reduced number of modules may be bound according to UCIE specifications for MMPL in the link initialization state **610**. In some instances, fewer than half of the modules have been successfully trained and the PHY repair state **812** may be entered at block **914**. After repair, the Link Speed state **810** may be entered at block **902**.

[0075] In some instances, one or more modules may report successful training with degraded speed. In these instances, it may be determined at block **908** whether better performance (e.g., better data throughput) can be obtained from a smaller number of link modules operating at the highest degraded speed than from all of the configured link modules when operating at a lowest degraded speed. If it is determined at block **908** that fewer modules are preferable, then the decision may be taken to reduce the number of link modules to be configured at block **916** before entering the link initialization state **610** at block **912**. The reduced number of modules may be bound according to UCIE specifications for MMPL in the link initialization state **610**. If it is determined at block **908** that fewer modules are not preferable, then the data rate and clock frequency may be reduced for all link modules at block **910** before the Speed Idle state **802** is entered at block **918** before reentry to the Link Speed state **810** at block **902**.

[0076] According to certain UCIE specifications, training is performed in parallel and independently on all mainband links **406** using associated sideband links **408**. After successful training, the mainband links **406** may be bound in the link initialization state **610** to provide a multimodule link according to UCIE specifications for MMPL. One sideband link **408** is used to carry link status and control message for all segments of the multimodule link. UCIE specifications define procedures for handling link errors during normal operation of the multimodule link.

[0077] FIG. **10** illustrates certain aspects of link error handling in a multimodule link that uses four link modules to provide 256 data lanes. At a first point in time **1000**, the multimodule link is operating without error and all link modules **1002**, **1004**, **1006**, **1008** are active and available for transmitting or receiving data. At a second point in time **1010**, one link module **1016** has failed due to an unresolvable error condition, while the other three link modules **1012**, **1014**, **1018** are unaffected by errors and are, at least temporarily, available for transmitting or receiving data. According to certain UCIE specifications, the complete multimodule link is retrained and/or repaired. Consequently, at a third point in time **1020**, all link modules **1022**, **1024**, **1026**, **1028** have entered a retraining or repair state after determining that link module **1016** has failed. All link modules **1022**, **1024**, **1026**, **1028** are inactive and unavailable for transmitting or receiving data. At a fourth point in time **1030**, after a successful retraining process, the multimodule link is operating without error and all link modules **1032**, **1034**, **1036**, **1038** are returned to an active state and are available for transmitting or receiving data.

[0078] FIG. **11** is a state diagram **1100** that illustrates certain aspects of retraining defined by UCIE

specifications for a multimodule link that uses four link modules **1102**, **1104**, **1106**, **1108** to provide 256 data lanes. The link modules **1102**, **1104**, **1106**, **1108** may each be in an active state **1116a**, **1116b**, **1116c**, **1116d** and available for transmitting or receiving data when an error detected on one link module **1106** causes the link module **1106** to fail. According to certain UCIE specifications, the complete multimodule link is retrained and/or repaired in response to the detection of an error affecting a single link module **1106**. All link modules **1102**, **1104**, **1106**, **1108** transition to corresponding mainband training states **1112a**, **1112b**, **1112c**, **1112d**. When all of the link modules **1102**, **1104**, **1106**, **1108** have reported successful training, the link modules **1102**, **1104**, **1106**, **1108** transition to their corresponding link initialization states **1114a**, **1114b**, **1114c**, **1114d**. The link modules **1102**, **1104**, **1106**, **1108** may be bound according to UCIE specifications for MMPL in the link initialization states **1114a**, **1114b**, **1114c**, **1114d** before the link modules **1102**, **1104**, **1106**, **1108** return to the active state **1116a**, **1116b**, **1116c**, **1116d** and the multimodule link becomes available for transmitting or receiving data.

[0079] FIG. **12** is diagram **1200** that illustrates the effect on multimodule link availability for inter-chiplet communication when conventional UCIE specifications govern retraining after failure of one or more link module. In the illustrated example, two chiplets **1202**, **1204** are coupled through a multimodule link that uses four link modules to provide 256 data lanes. An error event **1210** affecting one link module may trigger a fault condition that renders all 256 data lanes inoperative while retraining is performed. When completion of retraining is indicated **1212**, the multimodule link may become fully active with 256 data lanes available for transmitting or receiving data.

[0080] In conventional systems, the multimodule link provides zero bandwidth during retraining. Retraining involves transmitting various different training patterns, which can cause the multimodule link to be inactive for prolonged periods of time and which can consume significant power. Latencies associated with retraining and increased power consumption are attributable to retraining functional link modules and the retraining may be considered both redundant and inefficient. Certain applications may be unable to tolerate complete loss of communication over the multimodule link during retraining. In one example, certain vehicle management systems require communication link availability at all times, particularly when the vehicle is being operated autonomously. Systems requiring high-availability communication links include systems that manage, control or respond to location sensors or cameras, systems that manage, control or respond to vehicle positioning and systems that manage, control or respond to vehicle drivetrain, braking, etc.

[0081] Certain aspects of this disclosure can provide high-availability communication links that continue to actively transmit and receive data while repairing or retraining one or more link modules in a multimodule link. The high-availability communication links can support inter-chiplet communication for advanced packaging options defined by UCIE specifications. Communication can be sustained through failure events affecting mainband or sideband links in a link module and can be maintained while the mainband or sideband is repaired and/or retrained.

[0082] In certain implementations, multimodule link configuration may be downgraded by excluding a failed link module and one or more other link modules until the failed link module has been repaired and/or retrained. In one example, link modules that have failed may be retrained at a data rate and frequency of associated clock signals defined for all link modules in the Link Speed state **810**. When the failed link module has been retrained, all of the link modules may enter a link initialization state to enable the multimodule link configuration to be upgraded. Increasing the number of link modules to be configured in a multimodule link may be referred to herein as upgrading the multimodule link configuration.

[0083] FIG. **13** illustrates certain aspects of a link error handling scheme for a multimodule inter-die communication link that may be implemented in accordance with certain aspects of this disclosure. The illustrated example relates to a system that includes two chiplets, each chiplet including four link modules that are configured according to UCIE specifications to provide 256

data lanes in each direction (i.e., transmit and receive). At a first point in time **1300**, the multimodule link is operating without error and all link modules **1302**, **1304**, **1306**, **1308** are active and available for transmitting or receiving data. At a second point in time **1310**, one link module **1316** has failed due to an unresolvable error condition, while the other three link modules **1302**, **1304**, **1308** are unaffected by errors and remain available for transmitting or receiving data.

[0084] According to certain aspects of this disclosure, a multimodule communication link may be downgraded to the next supported configuration when one or more failed link modules are being retrained. One or more of the functional link modules **1312**, **1314**, **1318** may be combined to provide the largest available number of data lanes in a downgraded configuration that is consistent with UCIE specifications. Any of the link modules **1312**, **1314** and/or **1318** that are not used in the downgraded configuration may be idled. In the illustrated example, the multimodule communication link can be reconfigured at a third point in time **1320** to exclude the link module **1326** that has failed and that is being repaired or retrained. The multimodule communication link may be reconfigured to exclude one functional link module **1328** in order to obtain a multimodule communication link that provides 128 data lanes consistent with UCIE specifications.

[0085] When the link module **1326** that failed has been retrained, all link modules **1322**, **1324**, **1326**, **1328** enter a link initialization state. The link modules **1322**, **1324**, **1326**, **1328** may be bound according to UCIE specifications for MMPL in the link in initialization state before the link modules **1322**, **1324**, **1326**, **1328** are returned to the active state and the multimodule communication link becomes available for transmitting or receiving data. At a fourth point in time **1330**, the multimodule communication link is operating without error and all link modules **1332**, **1334**, **1336**, **1338** are operating in an active state and are available for transmitting or receiving data.

[0086] FIG. **14** is a state diagram **1400** that illustrates certain aspects of a link error handling scheme for a multimodule inter-die communication link that may be implemented in accordance with certain aspects of this disclosure. The illustrated link error handling scheme is directed to a multimodule communication link that uses four link modules **1402**, **1404**, **1406**, **1408** to provide 256 data lanes when operating nominally. Each of the link modules **1402**, **1404**, **1406**, **1408** may be in an active state **1416a**, **1416b**, **1416c**, **1416d** and available for transmitting or receiving data when an error detected on one link module **1406** causes the link module **1406** to fail.

[0087] According to certain aspects of this disclosure, retraining and/or repair of the failed link module **1406** may be initiated by a transition **1410** to the mainband training state **1412**, while the remaining link modules **1402**, **1404**, **1408** continue to be active and available for transmitting or receiving data. The multimodule communication link may be downgraded to the next supported UCIE configuration when one or more failed link modules are being retrained. One or more of the remaining link modules **1402**, **1404**, **1408** may be combined to provide the largest available number of data lanes in a downgraded configuration that is consistent with UCIE specifications. Any of the link modules **1402**, **1404** and/or **1408** that are not used in the downgraded configuration may be idled.

[0088] When the link module **1406** that failed has been retrained, all link modules **1402**, **1404**, **1406**, **1408** may enter a link initialization state **1414a**, **1414b**, **1414c**, **1414d**. The link modules **1402**, **1404**, **1406**, **1408** may be bound according to UCIE specifications for MMPL in the link initialization state **1414a**, **1414b**, **1414c**, **1414d**. The resultant multimodule communication link is made available for transmitting or receiving data when the link modules **1402**, **1404**, **1406**, **1408** reenter the active state **1416a**, **1416b**, **1416c**, **1416d**.

[0089] FIG. **15** is diagram **1500** that illustrates the effect of the presently-disclosed link error handling scheme on multimodule link availability for inter-chiplet communication. Two chiplets **1502**, **1504** are coupled through a multimodule link that uses four link modules to provide 256 data lanes. An error event **1510** affecting one link module may trigger a fault condition that renders the 64 data lanes provided by the affected link module inoperative while retraining is performed. An

additional link module is idled when the multimodule communication link is downgraded to the next supported UCI_e configuration, resulting in a loss of a further 64 data lanes. The downgraded multimodule communication link configuration provides 128 data lanes for transmitting data and 128 data lanes for receiving data while the failed link module is being repaired and/or retrained. When the failed link module is repaired and/or retrained **1512**, all four link modules can be bound according to UCI_e specifications for MMPL to configure a multimodule communication link that provides 256 data lanes for transmitting data and 256 data lanes for receiving data.

[0090] As illustrated in FIG. **15**, the presently-disclosed link error handling scheme is available for the majority of the time needed to repair and/or retrain one or more failed link modules. A short interruption of communication may be experienced when all link modules have entered a link initialization state after the one or more failed link modules have been successfully repaired and/or retrained.

[0091] According to certain aspects of this disclosure, the presently disclosed link error handling scheme may be implemented in a multimodule inter-die communication interface under the control of a processor, microcontroller or a finite state machine. In one example, the link error handling scheme may be implemented using some combination of the FSMs **552**, **562** in each die **402**, **404** (see FIG. **5**), each link module **1402**, **1404**, **1406**, **1408** and/or in each PHY circuits **412**, **414**, **416**, **418** in a link module. In some examples, at least one FSM **552**, **562** may be configured to operate as an LTSSM that is compatible or consistent with UCI_e specifications.

[0092] Two or more FSMs **552**, **562** configured to implement the presently disclosed link error handling scheme may communicate using state information maintained in one or more registers, such as the control registers **554**, **564** illustrated in FIG. **5**. In one example, an 8-bit “MMPL_Link_upgrade” control register may be provided to indicate when all link modules **1402**, **1404**, **1406**, **1408** are required to enter the link initialization state link initialization state **1414a**, **1414b**, **1414c**, **1414d**. For example, entry to the link initialization state **1414a**, **1414b**, **1414c**, **1414d** may be indicated when a link module **1406** that failed has been retrained and is ready to transition from the training state **1412** to its corresponding the link initialization state **1414c**. Active link modules **1402**, **1404**, **1408** transition from the active state **1416a**, **1416b**, **1416d** to the corresponding link initialization state **1414a**, **1414b**, **1414d**.

[0093] Certain aspects of this disclosure can improve aggregate data throughput over a mainband link during retraining procedures. Certain aspects of this disclosure can decrease communication link latencies associated with repair and retraining following an error event affecting one or more link modules. Certain aspects of this disclosure can improve the efficiency of mainband link communications and maximize throughput while optimizing power consumption following detection of an error event affecting one or more link modules. Certain aspects of this disclosure provide a repair and/or retraining scheme that is based on, and is compatible with UCI_e specifications.

[0094] FIG. **16** is a flowchart **1600** of a method for operating an interconnection between chiplets in accordance with certain aspects of this disclosure. In some instances, the method is implemented using a processor, a controller, a finite state machine or some combination of processors, controllers and finite state machines.

[0095] At block **1602** in the illustrated method, data may be transmitted or received over a multimodule data communication link that uses a first plurality of link modules to provide data transmit lanes and data receive lanes. At block **1604** in the illustrated method, a failed link module in the first plurality of link modules may be retrained while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data. At block **1606** in the illustrated method, the multimodule data communication link may be reconfigured to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules. At block **1608** in the illustrated method, the multimodule data communication link may be reconfigured to use the first plurality of link

modules for transmitting or receiving the data after the failed link module has been successfully retrained.

[0096] In certain implementations, the first plurality of link modules includes a first number of link modules that is defined by UCIE specifications. The second plurality of link modules may include a second number of link modules that is defined by the UCIE specifications.

[0097] In one example, the second plurality of link modules excludes at least one link module in the first plurality of link modules that is active and available for transmitting or receiving the data. The second plurality of link modules may include a number or quantity of link modules that is defined based on the number of the other link modules in the first plurality of link modules that are active and available for transmitting or receiving data.

[0098] In certain implementations, the number of data transmit lanes and data receive lanes provided by each link module may be defined by UCIE specifications. In one example, each link module can be configured to provide 64 data transmit lanes and 64 data receive lanes in accordance with an advanced packaging option defined by the UCIE specifications. In another example, each link module can be configured to provide 16 data transmit lanes and 16 data receive lanes in accordance with a standard packaging option defined by the UCIE specifications.

[0099] In certain implementations, a controller or FSM may cause each link module in the first plurality of link modules to enter a link initialization state after the failed link module has been successfully retrained. Each link module in the first plurality of link modules may be bound to the multimodule data communication link in a corresponding link initialization state. A sideband link in one of the first plurality of link modules may be designated to transmit and receive link status and control messages for all bound link modules in the first plurality of link modules. A sideband link in one of the second plurality of link modules may be designated to transmit and receive link status and control messages for all bound link modules in the second plurality of link modules. In some examples, each link module in the first plurality of link modules is bound to the multimodule data communication link in accordance with UCIE specifications. The failed link module may be retrained in accordance with UCIE specifications.

[0100] The method illustrated in FIG. 16 may be executed in or using an IC device. The IC device may include multiple semiconductor dice mounted on a substrate. In certain applications, at least one semiconductor die may be stacked on at least one other semiconductor die within an IC package. Each semiconductor die includes at least one circuit block configured to implement a function of the IC device. The IC device may include a controller and a first plurality of link modules configured to provide data transmit lanes and data receive lanes in a multimodule data communication link.

[0101] The controller may be configured to retrain a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data, reconfigure the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules, and reconfigure the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained.

[0102] In certain implementations, the first plurality of link modules includes a first number of link modules that is defined by UCIE specifications. The second plurality of link modules may include a second number of link modules that is defined by the UCIE specifications. In one example, the second plurality of link modules excludes at least one link module in the first plurality of link modules that is active and available for transmitting or receiving the data. The second plurality of link modules may include a number or quantity of link modules that is defined based on the number of the other link modules in the first plurality of link modules that are active and available for transmitting or receiving data.

[0103] In certain implementations, the number of data transmit lanes and data receive lanes

provided by each link module may be defined by UCIe specifications. In one example, each link module can be configured to provide 64 data transmit lanes and 64 data receive lanes in accordance with an advanced packaging option defined by the UCIe specifications. In another example, each link module can be configured to provide 16 data transmit lanes and 16 data receive lanes in accordance with a standard packaging option defined by the UCIe specifications.

[0104] In certain implementations, the controller may be implemented using an FSM. The FSM may be configured to operate as an LTSSM in accordance with UCIe specifications. The FSM may cause each link module in the first plurality of link modules to enter a link initialization state after the failed link module has been successfully retrained. Each link module in the first plurality of link modules may be bound to the multimodule data communication link in a corresponding link initialization state. A sideband link in one of the first plurality of link modules may be designated to transmit and receive link status and control messages for all bound link modules in the first plurality of link modules. A sideband link in one of the second plurality of link modules may be designated to transmit and receive link status and control messages for all bound link modules in the second plurality of link modules. In some examples, each link module in the first plurality of link modules is bound to the multimodule data communication link in accordance with UCIe specifications. The failed link module may be retrained in accordance with UCIe specifications.

[0105] In various aspects of the disclosure, a processor-readable storage medium that stores code that, when executed by a processor causes a processing circuit to transmit or receive data over a multimodule data communication link that uses a first plurality of link modules to provide data transmit lanes and data receive lanes, retrain a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data, reconfigure the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules, and reconfigure the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained.

[0106] In certain implementations, the first plurality of link modules includes a first number of link modules that is defined by UCIe specifications. The second plurality of link modules may include a second number of link modules that is defined by the UCIe specifications. In one example, the second plurality of link modules excludes at least one link module in the first plurality of link modules that is active and available for transmitting or receiving the data. The second plurality of link modules may include a number or quantity of link modules that is defined based on the number of the other link modules in the first plurality of link modules that are active and available for transmitting or receiving data.

[0107] In certain implementations, the number of data transmit lanes and data receive lanes provided by each link module may be defined by UCIe specifications. In one example, each link module can be configured to provide 64 data transmit lanes and 64 data receive lanes in accordance with an advanced packaging option defined by the UCIe specifications. In another example, each link module can be configured to provide 16 data transmit lanes and 16 data receive lanes in accordance with a standard packaging option defined by the UCIe specifications.

[0108] In certain implementations, the code may further cause the processing circuit to transition each link module in the first plurality of link modules into a link initialization state after the failed link module has been successfully retrained. Each link module in the first plurality of link modules may be bound to the multimodule data communication link in a corresponding link initialization state. A sideband link in one of the first plurality of link modules may be designated to transmit and receive link status and control messages for all bound link modules in the first plurality of link modules. A sideband link in one of the second plurality of link modules may be designated to transmit and receive link status and control messages for all bound link modules in the second plurality of link modules. In some examples, each link module in the first plurality of link modules

is bound to the multimodule data communication link in accordance with UCIE specifications. The failed link module may be retrained in accordance with UCIE specifications.

[0109] Some implementation examples are described in the following numbered clauses: [0110] 1. A method for operating an interconnection between chiplets, comprising: transmitting or receiving data over a multimodule data communication link that uses a first plurality of link modules to provide data transmit lanes and data receive lanes; retraining a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data; reconfiguring the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules; and reconfiguring the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained. [0111] 2. The method as described in clause 1, wherein the first plurality of link modules includes a first number of link modules that is defined by Universal Chiplet Interconnect Express (UCIE) specifications and the second plurality of link modules includes a second number of link modules that is defined by the UCIE specifications. [0112] 3. The method as described in clause 1 or clause 2, wherein the second plurality of link modules excludes at least one link module in the first plurality of link modules that is active and available for transmitting or receiving the data. [0113] 4. The method as described in any of clauses 1-3, wherein the second plurality of link modules comprises a quantity of link modules that is defined based on number of the other link modules in the first plurality of link modules that are active and available for transmitting or receiving data. [0114] 5. The method as described in any of clauses 1-4, wherein a number of data transmit lanes and data receive lanes provided by each link module is defined by UCIE specifications. [0115] 6. The method as described in clause 5, wherein each link module is configured to provide 64 data transmit lanes and 64 data receive lanes in accordance with an advanced packaging option defined by the UCIE specifications. [0116] 7. The method as described in clause 5, wherein each link module is configured to provide 16 data transmit lanes and 16 data receive lanes in accordance with a standard packaging option defined by the UCIE specifications. [0117] 8. The method as described in any of clauses 1-7, further comprising: causing each link module in the first plurality of link modules to enter a link initialization state after the failed link module has been successfully retrained, wherein each link module in the first plurality of link modules is bound to the multimodule data communication link in a corresponding link initialization state. [0118] 9. The method as described in clause 8, further comprising: designating a sideband link in one of the first plurality of link modules to transmit and receive link status and control messages for all bound link modules in the first plurality of link modules; and designating a sideband link in one of the second plurality of link modules to transmit and receive link status and control messages for all bound link modules in the second plurality of link modules. [0119] 10. The method as described in clause 8 or clause 9, wherein each link module in the first plurality of link modules is bound to the multimodule data communication link in accordance with UCIE specifications. [0120] 11. The method as described in any of clauses 1-10, wherein the failed link module is retrained in accordance with UCIE specifications. [0121] 12. A processor-readable storage medium storing code thereon, the code when executed by a processor causes a processing circuit to: transmit or receive data over a multimodule data communication link that uses a first plurality of link modules to provide data transmit lanes and data receive lanes; retrain a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data; reconfigure the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules; and reconfigure the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained. [0122] 13. The processor-readable storage medium as described in clause

12, wherein the first plurality of link modules includes a first number of link modules that is defined by Universal Chiplet Interconnect Express (UCIe) specifications and the second plurality of link modules includes a second number of link modules that is defined by the UCIe specifications. [0123] 14. The processor-readable storage medium as described in clause 12 or clause 13, wherein the second plurality of link modules excludes at least one link module in the first plurality of link modules that is active and available for transmitting or receiving the data. [0124] 15. The processor-readable storage medium as described in any of clauses 12-14, wherein the second plurality of link modules comprises a quantity of link modules that is defined based on number of the other link modules in the first plurality of link modules that are active and available for transmitting or receiving data. [0125] 16. The processor-readable storage medium as described in any of clauses 12-15, wherein a number of data transmit lanes and data receive lanes provided by each link module is defined by UCIe specifications. [0126] 17. The processor-readable storage medium as described in clause 16, wherein each link module is configured to provide 64 data transmit lanes and 64 data receive lanes in accordance with an advanced packaging option defined by the UCIe specifications. [0127] 18. The processor-readable storage medium as described in clause 16, wherein each link module is configured to provide 16 data transmit lanes and 16 data receive lanes in accordance with a standard packaging option defined by the UCIe specifications. [0128] 19. The processor-readable storage medium as described in any of clauses 12-18, wherein the code further causes the processing circuit to: cause each link module in the first plurality of link modules to enter a link initialization state after the failed link module has been successfully retrained, wherein each link module in the first plurality of link modules is bound to the multimodule data communication link in a corresponding link initialization state. [0129] 20. The processor-readable storage medium as described in clause 19, wherein the code further causes the processing circuit to: designate a sideband link in one of the first plurality of link modules to transmit and receive link status and control messages for all bound link modules in the first plurality of link modules; and designate a sideband link in one of the second plurality of link modules to transmit and receive link status and control messages for all bound link modules in the second plurality of link modules. [0130] 21. The processor-readable storage medium as described in clause 19 or clause 20, wherein each link module in the first plurality of link modules is bound to the multimodule data communication link in accordance with UCIe specifications. [0131] 22. The processor-readable storage medium as described in any of clauses 12-21, wherein the failed link module is retrained in accordance with UCIe specifications. [0132] 23. A communication interface in a chiplet, comprising: a first plurality of link modules configured to provide data transmit lanes and data receive lanes in a multimodule data communication link; and a controller configured to: retrain a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data; reconfigure the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules; and reconfigure the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained. [0133] 24. The communication interface as described in clause 23, wherein the first plurality of link modules includes a first number of link modules that is defined by Universal Chiplet Interconnect Express (UCIe) specifications and the second plurality of link modules includes a second number of link modules that is defined by the UCIe specifications. [0134] 25. The communication interface as described in clause 23 or clause 24, wherein the second plurality of link modules excludes at least one link module in the first plurality of link modules that is active and available for transmitting or receiving the data. [0135] 26. The communication interface as described in any of clauses 23-25, wherein the second plurality of link modules comprises a quantity of link modules that is defined based on number of the other link modules in the first plurality of link modules that are active and available for transmitting or receiving data.

[0136] 27. The communication interface as described in any of clauses 23-26, wherein a number of data transmit lanes and data receive lanes provided by each link module is defined by UCIe specifications. [0137] 28. The communication interface as described in clause 27, wherein each link module is configured to provide 64 data transmit lanes and 64 data receive lanes in accordance with an advanced packaging option defined by the UCIe specifications. [0138] 29. The communication interface as described in clause 27, wherein each link module is configured to provide 16 data transmit lanes and 16 data receive lanes in accordance with a standard packaging option defined by the UCIe specifications. [0139] 30. The communication interface as described in any of clauses 23-29, wherein the controller is further configured to: cause each link module in the first plurality of link modules to enter a link initialization state after the failed link module has been successfully retrained, wherein each link module in the first plurality of link modules is bound to the multimodule data communication link in a corresponding link initialization state. [0140] 31. The communication interface as described in clause 30, wherein the controller is further configured to: designate a sideband link in one of the first plurality of link modules to transmit and receive link status and control messages for all bound link modules in the first plurality of link modules. [0141] 32. The communication interface as described in clause 30 or clause 31, wherein each link module in the first plurality of link modules is bound to the multimodule data communication link in accordance with UCIe specifications. [0142] 33. The communication interface as described in any of clauses 23-32, wherein the failed link module is retrained in accordance with UCIe specifications.

[0143] It is understood that the specific order or hierarchy of steps in the processes disclosed is an illustration of exemplary approaches. Based upon design preferences, it is understood that the specific order or hierarchy of steps in the processes may be rearranged. Further, some steps may be combined or omitted. The accompanying method claims present elements of the various steps in a sample order, and are not meant to be limited to the specific order or hierarchy presented.

[0144] The previous description is provided to enable any person skilled in the art to practice the various aspects described herein. Various modifications to these aspects will be readily apparent to those skilled in the art, and the generic principles defined herein may be applied to other aspects. Thus, the claims are not intended to be limited to the aspects shown herein, but is to be accorded the full scope consistent with the language claims, wherein reference to an element in the singular is not intended to mean “one and only one” unless specifically so stated, but rather “one or more.” Unless specifically stated otherwise, the term “some” refers to one or more. All structural and functional equivalents to the elements of the various aspects described throughout this disclosure that are known or later come to be known to those of ordinary skill in the art are expressly incorporated herein by reference and are intended to be encompassed by the claims. Moreover, nothing disclosed herein is intended to be dedicated to the public regardless of whether such disclosure is explicitly recited in the claims. No claim element is to be construed as a means plus function unless the element is expressly recited using the phrase “means for.”

Claims

1. A method for operating an interconnection between chiplets, comprising: transmitting or receiving data over a multimodule data communication link that uses a first plurality of link modules to provide data transmit lanes and data receive lanes; retraining a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data; reconfiguring the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules; and reconfiguring the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained.

2. The method of claim 1, wherein the first plurality of link modules includes a first number of link modules that is defined by Universal Chiplet Interconnect Express (UCIe) specifications and the second plurality of link modules includes a second number of link modules that is defined by the UCIe specifications.
3. The method of claim 1, wherein the second plurality of link modules excludes at least one link module in the first plurality of link modules that is active and available for transmitting or receiving the data.
4. The method of claim 1, wherein the second plurality of link modules comprises a quantity of link modules that is defined based on number of the other link modules in the first plurality of link modules that are active and available for transmitting or receiving data.
5. The method of claim 1, wherein a number of data transmit lanes and data receive lanes provided by each link module is defined by UCIe specifications.
6. The method of claim 5, wherein each link module is configured to provide 64 data transmit lanes and 64 data receive lanes in accordance with an advanced packaging option defined by the UCIe specifications.
7. The method of claim 1, wherein each link module is configured to provide 16 data transmit lanes and 16 data receive lanes in accordance with a standard packaging option defined by the UCIe specifications.
8. The method of claim 1, further comprising: causing each link module in the first plurality of link modules to enter a link initialization state after the failed link module has been successfully retrained, wherein the failed link module is retrained in accordance with UCIe specifications, and wherein each link module in the first plurality of link modules is bound to the multimodule data communication link in a corresponding link initialization state.
9. The method of claim 8, further comprising: designating a sideband link in one of the first plurality of link modules to transmit and receive link status and control messages for all bound link modules in the first plurality of link modules; and designating a sideband link in one of the second plurality of link modules to transmit and receive link status and control messages for all bound link modules in the second plurality of link modules.
10. A communication interface in a chiplet, comprising: a first plurality of link modules configured to provide data transmit lanes and data receive lanes in a multimodule data communication link; and a controller configured to: retrain a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data; reconfigure the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules; and reconfigure the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained.
11. The communication interface of claim 10, wherein the first plurality of link modules includes a first number of link modules that is defined by Universal Chiplet Interconnect Express (UCIe) specifications and the second plurality of link modules includes a second number of link modules that is defined by the UCIe specifications.
12. The communication interface of claim 10, wherein the second plurality of link modules excludes at least one link module in the first plurality of link modules that is active and available for transmitting or receiving the data.
13. The communication interface of claim 10, wherein the second plurality of link modules comprises a quantity of link modules that is defined based on number of the other link modules in the first plurality of link modules that are active and available for transmitting or receiving data.
14. The communication interface of claim 10, wherein a number of data transmit lanes and data receive lanes provided by each link module is defined by UCIe specifications.
15. The communication interface of claim 14, wherein each link module is configured to provide

64 data transmit lanes and 64 data receive lanes in accordance with an advanced packaging option defined by the UCIe specifications.

16. The communication interface of claim 14, wherein each link module is configured to provide 16 data transmit lanes and 16 data receive lanes in accordance with a standard packaging option defined by the UCIe specifications.

17. The communication interface of claim 10, wherein the controller is further configured to: cause each link module in the first plurality of link modules to enter a link initialization state after the failed link module has been successfully retrained, wherein the failed link module is retrained in accordance with UCIe specifications, and wherein each link module in the first plurality of link modules is bound to the multimodule data communication link in a corresponding link initialization state.

18. The communication interface of claim 17, wherein the controller is further configured to: designate a sideband link in one of the first plurality of link modules to transmit and receive link status and control messages for all bound link modules in the first plurality of link modules; and designate a sideband link in one of the second plurality of link modules to transmit and receive link status and control messages for all bound link modules in the second plurality of link modules.

19. A processor-readable storage medium storing code thereon, the code when executed by a processor causes a processing circuit to: transmit or receive data over a multimodule data communication link that uses a first plurality of link modules to provide data transmit lanes and data receive lanes; retrain a failed link module in the first plurality of link modules while one or more other link modules in the first plurality of link modules are active and available for transmitting or receiving data; reconfigure the multimodule data communication link to use a second plurality of link modules that excludes the failed link module and includes fewer link modules than the first plurality of link modules; and reconfigure the multimodule data communication link to use the first plurality of link modules for transmitting or receiving the data after the failed link module has been successfully retrained.

20. The processor-readable storage medium of claim 19, wherein the code further causes the processing circuit to: cause each link module in the first plurality of link modules to enter a link initialization state after the failed link module has been successfully retrained, wherein the failed link module is retrained in accordance with Universal Chiplet Interconnect Express (UCIe) specifications, and wherein each link module in the first plurality of link modules is bound to the multimodule data communication link in a corresponding link initialization state.
