

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12387376
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Le; Nguyen Thang Long et al.

Dynamic calibration correction in multi-frame, multi-exposure capture

Abstract

A method includes obtaining a reference image frame and a non-reference image frame and generating a mask based on the reference image frame and the non-reference image frame. The method also includes determining a scaling coefficient and an offset coefficient for each of multiple color channels of the non-reference image frame based on pixels in the reference image frame and pixels in the non-reference image frame that are identified by the mask. The method further includes applying the scaling and offset coefficients to the non-reference image frame in order to generate a calibration-corrected non-reference image frame.

Inventors: Le; Nguyen Thang Long (Richardson, TX), Glotzbach; John William (Allen, TX), Sheikh; Hamid Rahim (Allen, TX)

Applicant: Samsung Electronics Co., Ltd. (Suwon-si, KR)

Family ID: 82323177

Assignee: Samsung Electronics Co., Ltd. (Suwon-si, KR)

Appl. No.: 18/410511

Filed: January 11, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240144534 A1	May. 02, 2024

Related U.S. Application Data

continuation parent-doc US 17573031 20220111 US 11989913 child-doc US 18410511
us-provisional-application US 63136840 20210113

Publication Classification

Int. Cl.: **G06T7/80** (20170101); **G06T5/50** (20060101); **G06T7/90** (20170101); **H04N9/77** (20060101); **H04N23/76** (20230101)

U.S. Cl.:

CPC **G06T7/80** (20170101); **G06T5/50** (20130101); **G06T7/90** (20170101); **H04N9/77** (20130101); **H04N23/76** (20230101); G06T2207/10024 (20130101); G06T2207/10144 (20130101)

Field of Classification Search

CPC: G06T (2207/10024); G06T (2207/10144); G06T (5/50); G06T (7/80); G06T (7/90); H04N (17/002); H04N (23/76); H04N (9/77)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9224190	12/2014	Moon et al.	N/A	N/A
9516290	12/2015	Lin et al.	N/A	N/A
9866727	12/2017	Wang et al.	N/A	N/A
10664960	12/2019	Lee	N/A	N/A
2015/0195441	12/2014	Chen et al.	N/A	N/A
2015/0350513	12/2014	Zhang et al.	N/A	N/A
2017/0358092	12/2016	Bleibel et al.	N/A	N/A
2017/0359534	12/2016	Li et al.	N/A	N/A
2023/0325999	12/2022	Dong et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
105844624	12/2015	CN	N/A
105844624	12/2017	CN	N/A
109479098	12/2018	CN	N/A
110163188	12/2018	CN	N/A
109218613	12/2019	CN	N/A
112132769	12/2019	CN	N/A
113994366	12/2021	CN	N/A
2017085407	12/2016	JP	N/A
2019176305	12/2018	JP	N/A
20080099731	12/2007	KR	N/A

OTHER PUBLICATIONS

International Search Report and Written Opinion of the International Searching Authority regarding International Patent Application No. PCT/KR2022/000628 dated May 3, 2022, 6 pages. cited by applicant

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application claims priority under 35 U.S.C. § 120 as a continuation of U.S. patent application Ser. No. 17/573,031 filed on Jan. 11, 2022, which claims priority under 35 U.S.C. § 119(e) to U.S. Provisional Patent Application No. 63/136,840 filed on Jan. 13, 2021, Both of these earlier applications are hereby incorporated by reference in their entirety.

TECHNICAL FIELD

(1) This disclosure relates generally to image processing. More specifically, this disclosure relates to a method for dynamic calibration correction in multi-frame, multi-exposure capture in a camera system.

BACKGROUND

(2) With the popularity of mobile devices that include digital cameras, almost everyone can take a picture at any time. As the quality of the camera hardware in mobile devices has improved, users have begun to expect high quality photos from their devices. However, the camera hardware in mobile devices still has significant limitations, such as poor low light performance. In a multi-frame, multi-exposure camera system, the same sensor calibration setting is applied to all frames, regardless of their individual exposure. In other words, frames at different exposures are calibrated using a single set of settings (black level subtraction (BLS), white balance (WB), lens-shading corrected (LSC), etc.), which set is calibrated for default, standard exposure value EV0. In many cases, this single set of settings is an inadequate incorrect calibration for shortly exposed frames (“short frames”), and results in strong color/level-shilling of the short frames after digital gains are applied to the shortly exposed frames. The color/level shifting manifests in the final output of a multi-frame image processing system as blending artifacts.

SUMMARY

(3) Embodiments of the present disclosure provide a method for dynamic calibration correction in multi-frame, multi-exposure capture in a camera system.

(4) In one embodiment, a method includes obtaining a reference image frame and a non-reference image frame and generating a mask based on the reference image frame and the non-reference image frame. The method also includes determining a scaling coefficient and an offset coefficient for each of multiple color channels of the non-reference image frame based on pixels in the reference image frame and pixels in the non-reference image frame that are identified by the mask. The method further includes applying the scaling and offset coefficients to the non-reference image frame in order to generate a calibration-corrected non-reference image frame.

(5) In another embodiment, an electronic device includes a processor and a memory storing instructions. The instructions, when executed by the processor, cause the processor to obtain a reference image frame and a non-reference image frame and generate a mask based on the reference image frame and the non-reference image frame. The instructions, when executed by the processor, also cause the processor to determine a scaling coefficient and an offset coefficient for each of multiple color channels of the non-reference image frame based on pixels in the reference image frame and pixels in the non-reference image frame that are identified by the mask. The instructions, when executed by the processor, further cause the processor to apply the scaling and offset coefficients to the non-reference image frame in order to generate a calibration-corrected non-reference image frame.

(6) In yet another embodiment, a non-transitory machine readable medium contains instructions

that when executed cause a processor to obtain a reference image frame and a non-reference image frame and generate a mask based on the reference image frame and the non-reference image frame. The non-transitory machine readable medium also contains instructions that when executed cause the processor to determine a scaling coefficient and an offset coefficient for each of multiple color channels of the non-reference image frame based on pixels in the reference image frame and pixels in the non-reference image frame that are identified by the mask. The non-transitory machine readable medium further contains instructions that when executed cause the processor to apply the scaling and offset coefficients to the non-reference image frame in order to generate a calibration-corrected non-reference image frame.

(7) Other technical features may be readily apparent to one skilled in the art from the following figures, descriptions, and claims.

(8) Before undertaking the DETAILED DESCRIPTION below, it may be advantageous to set forth definitions of certain words and phrases used throughout this patent document. The terms “transmit,” “receive,” and “communicate,” as well as derivatives thereof, encompass both direct and indirect communication. The terms “include” and “comprise,” as well as derivatives thereof, mean inclusion without limitation. The term “or” is inclusive, meaning and/or. The phrase “associated with,” as well as derivatives thereof, means to include, be included within, interconnect with, contain, be contained within, connect to or with, couple to or with, be communicable with, cooperate with, interleave, juxtapose, be proximate to, be bound to or with, have, have a property of, have a relationship to or with, or the like.

(9) Moreover, various functions described below can be implemented or supported by one or more computer programs, each of which is formed from computer readable program code and embodied in a computer readable medium. The terms “application” and “program” refer to one or more computer programs, software components, sets of instructions, procedures, functions, objects, classes, instances, related data, or a portion thereof adapted for implementation in a suitable computer readable program code. The phrase “computer readable program code” includes any type of computer code, including source code, object code, and executable code. The phrase “computer readable medium” includes any type of medium capable of being accessed by a computer, such as read only memory (ROM), random access memory (RAM), a hard disk drive, a compact disc (CD), a digital video disc (DVD), or any other type of memory. A “non-transitory” computer readable medium excludes wired, wireless, optical, or other communication links that transport transitory electrical or other signals. A non-transitory computer readable medium includes media where data can be permanently stored and media where data can be stored and later overwritten, such as a rewritable optical disc or an erasable memory device.

(10) As used here, terms and phrases such as “have,” “may have,” “include,” or “may include” a feature (like a number, function, operation, or component such as a part) indicate the existence of the feature and do not exclude the existence of other features. Also, as used here, the phrases “A or B,” “at least one of A and/or B,” or “one or more of A and/or B” may include all possible combinations of A and B. For example, “A or B,” “at least one of A and B,” and “at least one of A or B” may indicate all of (1) including at least one A, (2) including at least one B, or (3) including at least one A and at least one B. Further, as used here, the terms “first” and “second” may modify various components regardless of importance and do not limit the components. These terms are only used to distinguish one component from another. For example, a first user device and a second user device may indicate different user devices from each other, regardless of the order or importance of the devices. A first component may be denoted a second component and vice versa without departing from the scope of this disclosure.

(11) It will be understood that, when an element (such as a first element) is referred to as being (operatively or communicatively) “coupled with/to” or “connected with/to” another element (such as a second element), it can be coupled or connected with/to the other element directly or via a third element. In contrast, it will be understood that, when an element (such as a first element) is

referred to as being “directly coupled with/to” or “directly connected with/to” another element (such as a second element), no other element (such as a third element) intervenes between the element and the other element.

(12) As used here, the phrase “configured (or set) to” may be interchangeably used with the phrases “suitable for,” “having the capacity to,” “designed to,” “adapted to,” “made to,” or “capable of” depending on the circumstances. The phrase “configured (or set) to” does not essentially mean “specifically designed in hardware to.” Rather, the phrase “configured to” may mean that a device can perform an operation together with another device or parts. For example, the phrase “processor configured (or set) to perform A, B, and C” may mean a generic-purpose processor (such as a CPU or application processor) that may perform the operations by executing one or more software programs stored in a memory device or a dedicated processor (such as an embedded processor) for performing the operations.

(13) The terms and phrases as used here are provided merely to describe some embodiments of this disclosure but not to limit the scope of other embodiments of this disclosure. It is to be understood that the singular forms “a,” “an,” and “the” include plural references unless the context clearly dictates otherwise. All terms and phrases, including technical and scientific terms and phrases, used here have the same meanings as commonly understood by one of ordinary skill in the art to which the embodiments of this disclosure belong. It will be further understood that terms and phrases, such as those defined in commonly-used dictionaries, should be interpreted as having a meaning that is consistent with their meaning in the context of the relevant art and will not be interpreted in an idealized or overly formal sense unless expressly so defined here. In some cases, the terms and phrases defined here may be interpreted to exclude embodiments of this disclosure.

(14) Examples of an “electronic device” according to embodiments of this disclosure may include at least one of a smartphone, a tablet personal computer (PC), a mobile phone, a video phone, an e-book reader, a desktop PC, a laptop computer, a netbook computer, a workstation, a personal digital assistant (PDA), a portable multimedia player (PMP), an MP3 player, a mobile medical device, a camera, or a wearable device (such as smart glasses, a head-mounted device (HMD)), electronic clothes, an electronic bracelet, an electronic necklace, an electronic accessory, an electronic tattoo, a smart mirror, or a smart watch). Other examples of an electronic device include a smart home appliance. Examples of the smart home appliance may include at least one of a television, a digital video disc (DVD) player, an audio player, a refrigerator, an air conditioner, a cleaner, an oven, a microwave oven, a washer, a drier, an air cleaner, a set-top box, a home automation control panel, a security control panel, a TV box (such as SAMSUNG HOMESYNC, APPLETV, or GOOGLE TV), a gaming console (such as an XBOX, PLAYSTATION, or NINTENDO), a smart speaker or speaker with an integrated digital assistant (such as SAMSUNG GALAXY HOME, APPLE HOMEPOD, or AMAZON ECHO), an electronic dictionary, an electronic key, a camcorder, or an electronic picture frame.

(15) Still other examples of an electronic device include at least one of various medical devices (such as diverse portable medical measuring devices (like a blood sugar measuring device, a heartbeat measuring device, or a body temperature measuring device), a magnetic resonance angiography (MRA) device, a magnetic resonance imaging (MRI) device, a computed tomography (CT) device, an imaging device, or an ultrasonic device), a navigation device, a global positioning system (GPS) receiver, an event data recorder (EDR), a flight data recorder (FDR), an automotive infotainment device, a sailing electronic device (such as a sailing navigation device or a gyro compass), avionics, security devices, vehicular head units, industrial or home robots, automatic teller machines (ATMs), point of sales (POS) devices, or Internet of Things (IoT) devices (such as a bulb, various sensors, electric or gas meter, sprinkler, fire alarm, thermostat, street light, toaster, fitness equipment, hot water tank, heater, or boiler). Other examples of an electronic device include at least one part of a piece of furniture or building/structure, an electronic board, an electronic signature receiving device, a projector, or various measurement devices (such as devices for

measuring water, electricity, gas, or electromagnetic waves). Note that, according to various embodiments of this disclosure, an electronic device may be one or a combination of the above-listed devices. According to some embodiments of this disclosure, the electronic device may be a flexible electronic device. The electronic device disclosed here is not limited to the above-listed devices and may include new electronic devices depending on the development of technology.

(16) In the following description, electronic devices are described with reference to the accompanying drawings, according to various embodiments of this disclosure. As used here, the term “user” may denote a human or another device (such as an artificial intelligent electronic device) using the electronic device.

(17) Definitions for other certain words and phrases may be provided throughout this patent document. Those of ordinary skill in the art should understand that in many if not most instances, such definitions apply to prior as well as future uses of such defined words and phrases.

(18) None of the description in this application should be read as implying that any particular element, step, or function is an essential element that must be included in the claim scope. The scope of patented subject matter is defined only by the claims. Moreover, none of the claims is intended to invoke 35 U.S.C. § 112(f) unless the exact words “means for” are followed by a participle. Use of any other term, including without limitation “mechanism,” “module,” “device,” “unit,” “component,” “element,” “member,” “apparatus,” “machine,” “system,” “processor,” or “controller,” within a claim is understood by the Applicant to refer to structures known to those skilled in the relevant art and is not intended to invoke 35 U.S.C. § 112(f).

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) For a more complete understanding of the present disclosure and its advantages, reference is now made to the following description taken in conjunction with the accompanying drawings, in which like reference numerals represent like parts:

(2) FIG. 1 illustrates an example network configuration including an electronic device in accordance with various embodiments of this disclosure;

(3) FIG. 2A illustrates a block diagram of dynamic calibration correction in a multi-frame, multi-exposure (MFME) capture camera system in accordance with an embodiment of this disclosure;

(4) FIG. 2B illustrates a block diagram of a MFME capture camera system without the dynamic calibration correction;

(5) FIG. 3A illustrates an output image with dynamic calibration correction in accordance with an embodiment of this disclosure;

(6) FIGS. 3B and 3C illustrate examples of unstable output images without dynamic calibration correction;

(7) FIG. 4 illustrates a block diagram of additional details of the MFME dynamic calibration correction unit in accordance with an embodiment of this disclosure; and

(8) FIGS. 5A and 5B illustrate a method for dynamic calibration correction in multi-frame, multi-exposure capture in a camera system in accordance with an embodiment of this disclosure.

DETAILED DESCRIPTION

(9) FIGS. 1 through 5B, discussed below, and the various embodiments used to describe the principles of the present disclosure in this patent document are by way of illustration only and should not be construed in any way to limit the scope of the disclosure. Those skilled in the art will understand that the principles of the present disclosure may be implemented in any suitably-arranged system or device.

(10) FIG. 1 illustrates an example network configuration **100** in accordance with this disclosure. The embodiment of the network configuration **100** shown in FIG. 1 is for illustration only. Other

embodiments could be used without departing from the scope of this disclosure. As shown in FIG. 1, according to embodiments of this disclosure, an electronic device **101** is included in the network configuration **100**. The electronic device **101** may include at least one of a bus **110**, a processor **120**, a memory **130**, an input/output (I/O) interface **150**, a display **160**, a communication interface **170**, or an event processing module **180**. The electronic device **101** may also include a speaker **190** and camera **195**. In some embodiments, the electronic device **101** may exclude at least one of the components or may add another component.

(11) The bus **110** may include a circuit for connecting the components **120-180** with one another and transferring communications (such as control messages and/or data) between the components. The processor **120** may include one or more of a central processing unit (CPU), an application processor (AP), or a communication processor (CP). The processor **120** may perform control on at least one of the other components of the electronic device **101** and/or perform an operation or data processing relating to communication.

(12) The memory **130** may include a volatile and/or non-volatile memory. For example, the memory **130** may store commands or data related to at least one other component of the electronic device **101**. According to embodiments of this disclosure, the memory **130** may store software and/or a program **140**. The program **140** may include, for example, a kernel **141**, middleware **143**, an application programming interface (API) **145**, and/or an application program (or “application”) **147**. At least a portion of the kernel **141**, middleware **143**, or API **145** may be denoted an operating system (OS). The applications **147** include a dynamic calibration correction in multi-frame, multi-exposure capture application **163** (“DCC app” **163**), which is described more particularly below.

(13) The kernel **141** may control or manage system resources (such as the bus **110**, processor **120**, or memory **130**) used to perform operations or functions implemented in other programs (such as the middleware **143**, API **145**, or application program **147**). The kernel **141** may provide an interface that allows the middleware **143**, API **145**, or application **147** to access the individual components of the electronic device **101** to control or manage the system resources. The middleware **143** may function as a relay to allow the API **145** or the application **147** to communicate data with the kernel **141**, for example. A plurality of applications **147** may be provided. The middleware **143** may control work requests received from the applications **147**, such as by allocating the priority of using the system resources of the electronic device **101** (such as the bus **110**, processor **120**, or memory **130**) to at least one of the plurality of applications **147**. The API **145** is an interface allowing the application **147** to control functions provided from the kernel **141** or the middleware **143**. For example, the API **133** may include at least one interface or function (such as a command) for file control, window control, image processing, or text control.

(14) The input/output interface **150** may serve as an interface that may, for example, transfer commands or data input from a user or other external devices to other component(s) of the electronic device **101**. Further, the input/output interface **150** may output commands or data received from other component(s) of the electronic device **101** to the user or the other external devices.

(15) The display **160** may include, for example, a liquid crystal display (LCD), a light emitting diode (LED) display, an organic light emitting diode (OLED) display, a microelectromechanical systems (MEMS) display, or an electronic paper display. The display **160** can also be a depth-aware display, such as a multi-focal display. The display **160** may display various contents (such as text, images, videos, icons, or symbols) to the user. The display **160** may include a touchscreen and may receive, for example, a touch, gesture, proximity, or hovering input using an electronic pen or a body portion of the user.

(16) The communication interface **170** may set up communication between the electronic device **101** and an external electronic device (such as a first electronic device **102**, a second electronic device **104**, or a server **106**). For example, the communication interface **170** may be connected with a network **162** or **164** through wireless or wired communication to communicate with the external

electronic device.

(17) The first external electronic device **102** or the second external electronic device **104** may be a wearable device or an electronic device **101**-mountable wearable device (such as a head mounted display (HMD)). When the electronic device **101** is mounted in an HMD (such as the electronic device **102**), the electronic device **101** may detect the mounting in the MID and operate in a virtual reality mode. When the electronic device **101** is mounted in the electronic device **102** (such as the HMD), the electronic device **101** may communicate with the electronic device **102** through the communication interface **170**. The electronic device **101** may be directly connected with the electronic device **102** to communicate with the electronic device **102** without involving with a separate network.

(18) The wireless communication may use at least one of, for example, long term evolution (LTE), long term evolution-advanced (LTE-A), code division multiple access (CDMA), wideband code division multiple access (WCDMA), universal mobile telecommunication system (UMTS), wireless broadband (WiBro), or global system for mobile communication (GSM), as a cellular communication protocol. The wired connection may include at least one of, for example, universal serial bus (USB), high-definition multimedia interface (HDMI), recommended standard 232 (RS-232), or plain old telephone service (POTS). The network **162** may include at least one communication network, such as a computer network (like a local area network (LAN) or wide area network (WAN)), the Internet, or a telephone network.

(19) The first and second external electronic devices **102** and **104** each may be a device of the same type or a different type from the electronic device **101**. According to embodiments of this disclosure, the server **106** may include a group of one or more servers. Also, according to embodiments of this disclosure, all or some of the operations executed on the electronic device **101** may be executed on another or multiple other electronic devices (such as the electronic devices **102** and **104** or server **106**). Further, according to embodiments of this disclosure, when the electronic device **101** should perform some function or service automatically or at a request, the electronic device **101**, instead of executing the function or service on its own or additionally, may request another device (such as electronic devices **102** and **104** or server **106**) to perform at least some functions associated therewith. The other electronic device (such as electronic devices **102** and **104** or server **106**) may execute the requested functions or additional functions and transfer a result of the execution to the electronic device **101**. The electronic device **101** may provide a requested function or service by processing the received result as it is or additionally. To that end, a cloud computing, distributed computing, or client-server computing technique may be used, for example.

(20) The camera **195** enables the capture of photographs including frames at different exposures. More particularly, the camera **195** includes a multi-frame, multi-exposure camera system that simultaneously captures multiple frames of the same scene at different exposures. For example, the camera **195** could include the hardware, such as one or more lenses, a photodetector element, and other components used to convert light into a digital image. The camera **195** may additionally include specialized processors for performing various functions related to capturing photographs, or the camera **195** may use the processor **120** for these purposes.

(21) As introduced above, the DCC app **163** utilizes multiple frames captured by the camera **165** at different exposures to generate a single output image that dynamically calibrates (or re-calibrates) a multi-frame processor (MFP). The MFP receives and blends two or more frames into a single final output image. The goal of the MFP is to combine the multiple frames received into an output image with reduced noise compared to the inputs. Dynamic calibration correction enables the MFP to generate stable output while consuming few computing resources. Without the dynamic calibration correction provided by the DCC app **163**, a multi-frame, multi-exposure imaging system can be unstable due to the MFP exhibiting random bias in blending an EV0 frame with un-calibrated non-EV0 frames. The DCC app **163** enables the MFP to provide a higher dynamic range image with no blending artifacts compared to low-dynamic range images produced by the MFP without the DCC

app 163.

(22) While FIG. 1 shows that the electronic device **101** includes the communication interface **170** to communicate with the external electronic device **102** or **104** or server **106** via the network(s) **162** and **164**, the electronic device **101** may be independently operated without a separate communication function, according to embodiments of this disclosure. Also, note that the electronic device **102** or **104** or the server **106** could be implemented using a bus, a processor, a memory, I/O interface, a display, a communication interface, and an event processing module (or any suitable subset thereof) in the same or similar manner as shown for the electronic device **101**.

(23) The server **106** may operate to drive the electronic device **101** by performing at least one of the operations (or functions) implemented on the electronic device **101**. For example, the server **106** may include an event processing server module (not shown) that may support the event processing module **180** implemented in the electronic device **101**. The event processing server module may include at least one of the components of the event processing module **180** and perform (or instead perform) at least one of the operations (or functions) conducted by the event processing module **180**. The event processing module **180** may process at least part of the information obtained from other elements (such as the processor **120**, memory **130**, input/output interface **150**, or communication interface **170**) and may provide the same to the user in various manners.

(24) In some embodiments, the processor **120** or event processing module **180** is configured to communicate with the server **106** to download or stream multimedia content, such as images, video, or sound. For example, a user operating the electronic device **101** can open an application or website to stream multimedia content. The processor **120** (or event processing module **180**) can process and present information, via the display **160**, to enable a user to search for content, select content, and view content. In response to the selections by the user, the server **106** can provide the content or record the search, selection, and viewing of the content, or both provide and record.

(25) While the event processing module **180** is shown to be a module separate from the processor **120** in FIG. 1, at least a portion of the event processing module **180** may be included or implemented in the processor **120** or at least one other module, or the overall function of the event processing module **180** may be included or implemented in the processor **120** shown or another processor. The event processing module **180** may perform operations according to embodiments of this disclosure in interoperation with at least one program **140** stored in the memory **130**.

(26) Although FIG. 1 illustrates one example of a network configuration **100**, various changes may be made to FIG. 1. For example, the network configuration **100** could include any number of each component in any suitable arrangement. In general, computing and communication systems come in a wide variety of configurations, and FIG. 1 does not limit the scope of this disclosure to any particular configuration. Also, while FIG. 1 illustrates one operational environment in which various features disclosed in this patent document can be used, these features could be used in any other suitable system.

(27) FIG. 2A illustrates a block diagram of dynamic calibration correction (DCC) in a multi-frame, multi-exposure (MFME) capture camera system **200** in accordance with an embodiment of this disclosure. The embodiment of the DCC in the MFME capture camera system **200** shown in FIG. 2A is for illustration only. Other embodiments of the DCC in the MFME capture camera system **200** could be used without departing from the scope of this disclosure. In certain embodiments, the MFME capture camera system **200** is the same as, or implemented by, camera **195**.

(28) The camera system **200** includes an amplifier **210** and a multi-frame processor **220**. When the camera **165** captures an image of a scene, the camera **165** simultaneously captures a reference frame **230** and a non-reference frame **240**. The reference frame **230** is captured at a standard exposure value (EV0) and the non-reference frame **240** is captured at a different exposure value, such as EV-4 or EV-2. The amplifier **210** receives the non-reference frame **240** as input. The amplifier **210** further, based on the input, generates and outputs an amplified non-reference frame

250 by applying a digital gain (for example, $4\times$ or $16\times$) to the original non-reference frame 240. In the example shown in FIG. 2A, the original non-reference frame 240 is captured at an exposure value EV-4. The amplifier 210 applies a $16\times$ digital gain. Based on the applied $16\times$ digital gain, the amplified non-reference frame 250 may also be referred to as a $16\times$ EV-4 frame. The camera 195 utilizes a shorter exposure duration at EV-4 compared to the standard exposure duration at EV0, and for simplicity, the original non-reference frame 240 captured at EV-4 is also referred to as the original "short frame." The shorter exposure duration at EV-4 causes the original short frame 240 to be dark (including darker pixels) as compared to the brighter reference frame 230.

(29) In accordance with embodiments of this disclosure, the camera system 200 includes a DCC unit 300 that dynamically calibrates the MFP 220 by providing a calibration-corrected amplified non-reference frame 260 to the MFP 220. The DCC unit 300 includes DCC app 163, which performs the functions of the DCC app of FIG. 1. As inputs, the DCC unit 300 receives the reference frame 230 and the amplified non-reference frame 250. The function of the DCC unit 300 is described further with reference to FIG. 4.

(30) The MFP 220 receives and blends the reference frame 230 and the calibration-corrected amplified non-reference frame 260 into a single output image 270. The output image 270 exhibits the correction provided by the DCC unit 300.

(31) Although FIG. 2A illustrates an example DCC unit 300 in the MFME capture camera system 200, various changes may be made to FIG. 2A. For example, various components in FIG. 2A could be combined, further subdivided, or omitted and additional components could be added according to particular needs. As a particular example, the MFP 220 could incorporate the DCC unit 300.

(32) FIG. 2B illustrates a block diagram of a DCC in the MFME capture camera system 201 without the dynamic calibration correction. FIG. 2B is provided for comparison to the technical advantages provided by the DCC unit 300 of FIG. 2A.

(33) A MFME camera system 201 includes the amplifier 210 and the multi-frame processor 220. In certain embodiments, the MFME camera system 201 is the same as, or implemented by, camera 195. The MFP 220 receives and blends the reference frame 230 and the amplified non-reference frame 250 into a single output image 280. The MFME camera system 201 outputs an output image 280 that exhibits blending artifacts as a result of color/level-shifting after digital gain application on shortly exposed frames. Without the dynamic calibration correction provided by the DCC unit 300, the MFME camera system 201 can be unstable due to the MFP 220 exhibiting random bias in blending an EV0 frame with un-calibrated non-EV0 frames. That is, the output image 280, which is generated by the MFP 220 blending the reference image 230 with the amplified non-reference frame 250, can be a first unstable output image 280a, such as the example shown in FIG. 3B, or can be a second unstable output image 280b, such as the example shown in FIG. 3C. When the frame 250 that is used to calibrate the MFP 220 for reducing noise is inadequately calibrated for the EV0 reference frame 230, then the MFP 220 will produce a poor quality, unstable output image 280 (280a or 280b).

(34) For ease of visibility, FIGS. 3A-3C provide larger views of the final output image of the MFP 220. FIG. 3A illustrates the output image 270 with dynamic calibration correction in accordance with an embodiment of this disclosure. As shown in FIG. 3A, the DCC unit 300 enables the MFP 220 to generate stable output with minimal calibration effort for the input. For example, the minimal calibration effort can correspond to a consumption of few computing resources. In certain embodiments, the DCC unit 300 enables the MFP 220 to generate stable output with minimal off-line calibration effort for the input, where off-line calibration refers to calibration at the time of manufacture. FIGS. 3B and 3C illustrate examples of unstable output images 280a and 280b without dynamic calibration correction. In FIG. 3B, the output image 280a exhibits color artifacts in the final output from the MFP 220 due to incorrect calibration of short exposure frames. The color artifacts exhibited can include color casting such as a pink colored cast. In FIG. 3C, the output image 280b exhibits bright colored pixels (within the outline 282) on the person's white

jacket where the reference frame **230** includes white pixels that represent the actual color of the person's jacket.

(35) FIG. **4** illustrates a block diagram of additional details of the MFME dynamic calibration correction unit **300** in accordance with an embodiment of this disclosure. The embodiment of the DCC unit **300** shown in FIG. **4** is for illustration only. Other embodiments of the DCC unit **300** could be used without departing from the scope of this disclosure.

(36) It is expensive and laborious to calibrate different settings for different frames in a multi-frame, multi-exposure system. As a technical solution, the DCC unit **300** performs dynamic/online re-calibration correction of shortly exposed frames on the fly. That is, the DC unit **300** can perform the dynamic/online re-calibration correction within the time the reference and original short frames **230** and **240** are captured to the time of outputting the calibration-corrected frame **260**. The DCC unit **300** provides technical advantages in which runtime re-calibration of a black offset and/or color correction matrix for lower exposure frames uses information from the higher exposure frame, and runtime correction of lower exposure frames uses information from the higher exposure frame. The DCC unit **300** implements a method that uses information from standard exposure value EV0 frames to estimate the correction needed to apply on non-EV0/shortly exposed frames. The DCC unit **300** includes a mask generator **410**, a dynamic re-calibrator **420**, a dynamic corrector **430**, and a saturation-preserving blender **440**. In some embodiments, the DCC unit **300** also includes at least one lens shading correction remover **405** and a lens shading correction re-applicator **435**.

(37) The DCC unit **300** detects whether the reference frame **230** or the amplified non-reference frame **250** includes lens-shading corrected (ESC) data. The lens shading correction remover **405** removes LSC data detected in the reference frame **230** and removes LSC data detected in the amplified non-reference frame **250**.

(38) The mask generator **410** receives the reference frame **230** and the amplified non-reference frame **250** as inputs. In some embodiments, the mask generator **410** receives the reference frame and the amplified non-reference frame that no longer contain LSC data from the lens shading correction remover **405**. The mask generator **410** generates a mask **450** based on the received reference frame and the amplified non-reference frame. The mask **450** is a binary image in which white pixels indicate locations that are used for subsequent linear or non-linear estimation. The black pixels of the mask **450** represent pixel locations where the reference frame includes a saturated, white pixels that may be excluded from linear or non-linear estimation the dynamic re-calibrator **420** performs. A white pixel has the value **255** at each of the R, G, and B channels. Each mask represents the luma components of an image from which the chroma components have been removed. In some embodiments, the mask **450** is defined by Equation 1 based on the intersection of the luma-based masks of the reference frame **230** and the amplified non-reference frame **250**. That is, the location of a white pixel in the mask **450** indicates that a white pixel is at the same location in both the luma-based mask of the reference frame **230** and the luma-based mask of the amplified non-reference frame **250**.

$$\text{mask} = \text{mask.sub.ref} \cdot \text{Math.mask.sub.nonRef} \quad (1)$$

(39) To generate the mask **450**, the mask generator **410** computes a reference mask (mask.sub.ref) based on luma of the reference frame in accordance with Equation 2 and computes a non-reference mask (mask.sub.nonRef) based on luma of the amplified non-reference frame in accordance with Equation 3. More particularly, the mask generator **410** computes the reference mask is based on a comparison of a reference luma threshold (threshold.sub.ref) to the luma (luma.sub.ref) of the reference frame. Similarly, the mask generator **410** computes the non-reference mask based on a comparison of a non-reference luma threshold (threshold.sub.NonRef) to the luma (luma.sub.ref) of the amplified non-reference frame **250**. In some embodiments, the luma threshold (threshold.sub.ref or threshold.sub.NonRef) indicates a designer-specified value (e.g., less than 255) above which the pixel value is considered saturated.

$$\text{mask.sub.ref} = \text{luma.sub.ref} \leq \text{threshold.sub.ref} \quad (2)$$

$$\text{mask.sub.NonRef} = \text{luma.sub.NonRef} \leq \text{threshold.sub.NonRef} \quad (3)$$

(40) In the embodiment shown FIG. 4, the mask generator **410** computes the luma of the amplified non-reference frame by averaging R, G, and B channels of the amplified non-reference frame. The mask generator **410** computes the luma of the reference frame by averaging R, G, and B channels of the reference frame. It is understood that this disclosure is not limited to image processing in the red-green-blue (RGB) domain (including R, G, and B channels), and that embodiments of this disclosure include image processing in other domains that include a number of channels. For example, some embodiments of this disclosure include processing images according to a number of channels of a Bayer domain.

(41) The dynamic re-calibrator **420** receives the mask **450**, the reference frame **230**, and the amplified non-reference frame **250** as inputs. Based on the inputs **230**, **250**, and **450**, the dynamic re-calibrator **420** estimates a scaling coefficient (a) and an offset coefficient (b) for each of a number of channels in the domain (e.g., RGB, Bayer, etc.) corresponding to received frames (i.e., reference frame **230** and amplified non-reference frame **250**). For example, the dynamic re-calibrator **420** estimates a scaling coefficient a.sub.R, a.sub.G, and a.sub.B corresponding to each of the R, G, and B channels in the RGB domain, respectively. Also, the dynamic re-calibrator **420** estimates an offset coefficient b.sub.R, b.sub.G, and b.sub.B corresponding to each of the R, G, and B channels in the RGB domain, respectively. To generate the scaling and offset coefficients, the dynamic re-calibrator **420** selects pixel locations from the mask **450** where a pixel is white. Each pixel location in the mask **450** corresponds to a pair of pixels (r, n) at an identical pixel location in the reference frame **230** and amplified non-reference frame **250**. In certain embodiments, the dynamic re-calibrator **420** estimates the scaling and offset coefficients by applying a noisy linear model to the pairs of pixels at the selected locations. The noisy linear model defines the relationship between pixels (r) in the reference frame **230** and pixels (n) in the amplified non-reference frame **250** that are at the selected pixel locations. An example noisy linear model is defined by Equation 4, where ϵ represents noise. The dynamic re-calibrator **420** fits the linear model to the pair of pixels (r, n). In certain embodiments, the dynamic re-calibrator **420** estimates the scaling and offset coefficients based on a specified objective, such as the objective defined by Equation 5. The specified objective is applied to each of the R, G, and B channels. The specified objective can be a matching criterion. In Equation 5, the sum of the total square error between the pair of pixels (r, n) is minimized while solving to determine scaling and offset coefficients a and b.

$$(42) \quad r = (a \cdot \text{Math. } n + b + \epsilon)^2 \quad (4) \quad \text{objective} = \min_{a,b} \cdot \text{Math.}_{r,n} (r - a \cdot \text{Math. } n - b)^2 \quad (5)$$

(43) The dynamic corrector **430** receives and the scaling and offset coefficients ({a.sub.R and b.sub.R}, {a.sub.G and b.sub.G}, and {a.sub.B and b.sub.B}) from the dynamic re-calibrator **420** and the amplified non-reference frame **250** as inputs. The dynamic corrector **430** generates an intermediate calibration-correction (ICC) frame **480** by applying a calibration correction model to the amplified non-reference frame **250** for each of the R, G, and B channels. The calibration correction/regression model can be a linear calibration correction model or a non-linear calibration correction model. For ease of explanation, the DCC unit **330** will be described as applying a linear calibration correction model in which each of the R, G, and B channels of the amplified non-reference frame **250** has a corresponding scaling coefficient applied as a multiplier and a corresponding offset coefficient applied as an addition. Particularly, the dynamic corrector **430** multiplies a first scaling coefficient a.sub.R by the first channel, such as the R channel, of the amplified non-reference frame **250** and adds the first offset coefficient b.sub.R to the resulting product. Additionally, the dynamic corrector **430** multiplies a second scaling coefficient a.sub.G by the second channel, such as the G channel of the amplified non-reference frame **250** and adds the second offset coefficient b.sub.G, and analogously applies the third scaling and offset coefficients a.sub.B and b.sub.B to the third channel, such as the B channel, of the amplified non-reference

frame **250**. After applying the calibration correction model, the saturation area of the ICC frame **480** might be distorted. That is, the ICC frame **480** is a linear calibration-corrected non-reference frame, which includes calibration correction without saturation preservation. To preserve the saturation area, these distortion areas are detected and the blended back into the ICC frame **480** by the saturation-preserving blender **440**.

(44) The DCC unit **300** applies the linear calibration correction model on linear data. In certain embodiments, the DCC unit **300** prevents application of the linear calibration correction model onto lens-shading corrected (ESC) data. Particularly, if the reference and non-reference frames **230** and **250** are lens-shading corrected, then the lens shading correction remover **405** removes the LSC data from both the reference and non-reference frames **230** and **250** before the mask generator **410** generates the mask **450**, and the lens shading correction re-applicator **435** re-applies LSC data onto the ICC frame **480**, but before the saturation-preserving blender **440** performs saturation-preserving blending.

(45) The saturation-preserving blender **440** preserves a saturation area of the amplified non-reference frame **250** by detecting the saturation area of the amplified non-reference frame **250**, and blending the detected saturation area into the calibration-corrected amplified non-reference frame. To detect the saturation area, the saturation-preserving blender **440** generates a saturation map (satMap) based on a saturation threshold value (satThr) and saturation slope (satSlope). Particularly, the saturation-preserving blender **440** generates a saturation map (satMap) by suppressing, at each pixel(s) in the amplified short frame **250**, the highest value (max.sub.RGB) from among the R, G, B values. The saturation threshold value is a designer-specified value, such as the value **200**. The saturation slope is designer-specified value, such as the value **50**, which smooths the transition from saturation to non-saturation. The saturation-preserving blender **440** generates the calibration-corrected amplified non-reference frame **260** by blending the amplified short frame **250** (ShortFrame) with the ICC frame **480** (nonRef.sub.corrected), using the saturation reap. That is, under the guidance of the saturation map, the saturation-preserving blender **440** preserves a saturation area of the amplified non-reference frame **250** by combining the non-reference frame without (prior to) calibration correction together with the ICC frame **480** with (after applying) calibration correction. For each pixel represented in the saturation map, the satMap value that is greater than or equal to zero (0) and less than or equal to one (1). In certain embodiments, saturation-preserving blender **440** generates a saturation map defined by Equation 6. The saturation-preserving blender **440** generates and outputs the calibration-corrected amplified non-reference frame **260** in accordance with Equation 7.

$$(46) \quad \text{satMap} = \max(0, \min(1, \frac{\max_{\text{RGB}}(S) - \text{satThr}}{\text{satSlope}})) \quad (6)$$

$$\text{output} = \text{satMap} \cdot \text{Math. ShortFrame} + (1 - \text{satMap}) \cdot \text{Math. nonRef}_{\text{corrected}} \quad (7)$$

(47) Although FIG. 4 illustrates an example of a DCC unit **300**, various changes may be made to FIG. 4. For example, various components in FIG. 4 could be combined, further subdivided, or omitted and additional components could be added according to particular needs. As a particular example, the lens shading correction re-applicator **435** and saturation-preserving blender **440** may be combined.

(48) FIGS. 5A and 5B illustrate a method for dynamic calibration correction in multi-frame, multi-exposure capture in a camera system in accordance with an embodiment of this disclosure. The method **500** is implemented by an electronic device **101** that includes the DCC unit **300**. More particularly, the method **500** could be performed by a processor **120** of the electronic device **101** executing the DCC app **163**. For ease of explanation, the method **500** is described as being performed by the processor **120**.

(49) In operation **502**, the processor **120** receives a non-reference frame with a digital gain applied and a reference frame as inputs. For simplicity of illustration, Frame.sub.Ref represents the reference frame **230**, and Frame.sub.nonRef represents the amplified non-reference frame **250**. In

operation **504**, a mask **450** is generated using the mask generator **410**. More particularly, to generate the mask **450**, the processor **120** computes a non-reference mask (at block **506**) and computes a reference mask (at block **508**). In operation **512**, the processor **120** computes the non-reference mask by computing the luma (luma.sub.NonRef) of the amplified non-reference frame **250** and comparing, in operation **512**, a non-reference luma threshold (threshold.sub.NonRef) to the luma of the amplified non-reference frame **250**. To compute the reference mask, the processor **120**, in operation **514**, first computes the luma (luma.sub.ref) of the reference frame **230** and, in operation **516**, compares a reference luma threshold (threshold.sub.ref) to the luma of the reference frame **230** (at block **516**). In certain embodiments, computing the luma of a frame (e.g., luma.sub.NonRef or luma.sub.ref respectively) includes computing the average of the R, G, and B channels of the frame (e.g., amplified non-reference frame **250** or reference frame **230**, respectively). For example, computing the average of the channels includes computing the sum of the R, G, and B channels at each pixel in the frame, and divide by the number of channels (e.g., 3). In certain embodiments, the luma of an RGB image can be computed according to other methods.

(50) In operation **518**, for each of the RGB channels, the processor **120** estimates scaling and offset coefficients (a, b) based on the generated mask **450**. More particularly, operation **518** includes the operations **520**, **522**, and **524**. In operation **520**, a pixel location in the mask **450** is selected where a pixel is white. When selecting the pixel location in the mask, the processor **120** also selects the corresponding pair of pixels (r, n) at the identical pixel location in the reference and amplified-non reference frames **230** and **250**. That is, the selection of the pixel location also results in the selection of the pair of pixels (r, n). In operation **522**, the processor **120** applies a noisy linear model to the pairs of pixels. In operation **524**, the processor **120** estimates the coefficients based on the selected pairs of pixels (r, n) and a selected objective (e.g.; matching criteria).

(51) In operation **526**, the calibration of the amplified non-reference frame **250** is corrected by applying the scaling coefficients (a.sub.R, a.sub.G, and a.sub.B) and the offset coefficients (b.sub.R, b.sub.G, and b.sub.B). More particularly, the processor **120** corrects the calibration of the amplified non-reference frame **250** by using the dynamic corrector **430** to generate the ICC frame **480**.

(52) In operation **528**, the processor **120** re-applies LSC data to intermediate calibration-corrected frame **480** that no longer contain the LSC data that was removed by the lens shading correction remover **405**.

(53) In operation **530**, a saturation area of the amplified non-reference frame **250** is preserved. More particularly, to preserve the saturation area, the processor **120** can detect the saturation area of the amplified non-reference frame **250** (at block **532**), and blend the detected saturation area into the calibration-corrected non-reference frame referred to as ICC frame **480** (at block **534**). In certain embodiments, detecting the saturation area includes, in operation **536**, in suppressing a highest value among R, G, and B values at each pixel in the amplified short frame **250**. That is, to detect the saturation area, the processor **120** can suppress the highest values at each pixel. In certain embodiments, blending the detected saturation area into the ICC frame **480** includes operation **538**, in which the processor **120** uses the saturation map to blend the amplified short frame **250** and the calibration-corrected non-reference frame referred to as ICC frame **480**.

(54) In operation **540**, the processor **120** calibrates or re-calibrates a multi-frame processor **220** (MFP) by outputting the calibration-corrected amplified non-reference frame **260** to the MFP **220**. That is, the calibration-corrected amplified non-reference frame **260**, when received by the MFP **220**, configures the MFP **220** with correct calibration.

(55) In operation **542**, the MFP **220** generates and outputs a corrected image, which is referred to as the output image **270**. To generate the output image **270**, in operation **544**, the MFP **220** applies a correct calibration received from the DCC unit **300** to the reference frame **230** by blending the received calibration-corrected amplified non-reference frame **260** into the reference frame **230**.

(56) The above flowcharts illustrate example methods that can be implemented in accordance with

the principles of the present disclosure and various changes could be made to the methods illustrated in the flowcharts herein. For example, while shown as a series of steps, various steps in each figure could overlap, occur in parallel, occur in a different order, or occur multiple times. In another example, steps may be omitted or replaced by other steps.

(57) Although the figures illustrate different examples of user equipment, various changes may be made to the figures. For example, the user equipment can include any number of each component in any suitable arrangement. In general, the figures do not limit the scope of this disclosure to any particular configuration(s). Moreover, while figures illustrate operational environments in which various user equipment features disclosed in this patent document can be used, these features can be used in any other suitable system.

(58) None of the description in this application should be read as implying that any particular element, step, or function is an essential element that must be included in the claim scope. The scope of patented subject matter is defined only by the claims. Moreover, none of the claims is intended to invoke 35 U.S.C. § 112(f) unless the exact words “means for” are followed by a participle. Use of any other term, including without limitation “mechanism,” “module,” “device,” “unit,” “component,” “element,” “member,” “apparatus,” “machine,” “system,” “processor,” or “controller,” within a claim is understood by the applicants to refer to structures known to those skilled in the relevant art and is not intended to invoke 35 U.S.C. § 112(f).

(59) Although the present disclosure has been described with exemplary embodiments, various changes and modifications may be suggested to one skilled in the art. It is intended that the present disclosure encompass such changes and modifications as fall within the scope of the appended claims. None of the description in this application should be read as implying that any particular element, step, or function is an essential element that must be included in the claims scope. The scope of patented subject matter is defined by the claims.

Claims

1. A method performed by an electronic device, the method comprising: obtaining, from at least one memory of the electronic device, a reference image frame and a non-reference image frame; generating, by at least one processor of the electronic device, a mask based on the reference image frame and the non-reference image frame; determining, by the at least one processor, a scaling coefficient and an offset coefficient for each of multiple color channels of the non-reference image frame based on pixels in the reference image frame and pixels in the non-reference image frame that are identified by the mask; and applying, by the at least one processor, the scaling and offset coefficients to the non-reference image frame in order to generate a calibration-corrected non-reference image frame.
2. The method of claim 1, further comprising: blending the reference image frame and the calibration-corrected non-reference image frame to generate an output image of a scene.
3. The method of claim 1, wherein: the reference image frame is associated with a first exposure duration; and the non-reference image frame is associated with a second exposure duration that is shorter than the first exposure duration.
4. The method of claim 1, wherein generating the mask comprises: generating a reference mask based on the reference image frame and a reference luma threshold; generating a non-reference mask based on the non-reference image frame and a non-reference luma threshold; and determining an intersection of the reference mask and the non-reference mask.
5. The method of claim 1, wherein determining the scaling coefficient and the offset coefficient for each of the color channels of the non-reference image frame comprises: identifying pairs of pixels based on the mask, each pair of pixels including one of the pixels of the reference image frame and one of the pixels of the non-reference image frame; fitting a noisy model to the pairs of pixels; and using an objective function that includes the model to determine the scaling coefficients and the

offset coefficients.

6. The method of claim 1, further comprising: detecting a saturation area of the non-reference image frame; and blending the detected saturation area into the calibration-corrected non-reference image frame.

7. The method of claim 6, further comprising: removing lens-shading corrected (LSC) data from at least one of the reference image frame or the non-reference image frame, the mask based on the reference image frame and the non-reference image frame that do not contain the LSC data; and re-applying the LSC data to the calibration-corrected non-reference image frame prior to blending the detected saturation area into the calibration-corrected non-reference image frame.

8. The method of claim 6, wherein: detecting the saturation area comprises suppressing a highest value among the color channels at each pixel location in the non-reference image frame and generating a saturation map; and blending the detected saturation area into the calibration-corrected non-reference image frame comprises blending the non-reference image frame and the calibration-corrected non-reference image frame based on the saturation map.

9. An electronic device comprising: at least one processor; and at least one memory storing instructions that, when executed by the at least one processor, cause the at least one processor to: obtain a reference image frame and a non-reference image frame; generate a mask based on the reference image frame and the non-reference image frame; determine a scaling coefficient and an offset coefficient for each of multiple color channels of the non-reference image frame based on pixels in the reference image frame and pixels in the non-reference image frame that are identified by the mask; and apply the scaling and offset coefficients to the non-reference image frame in order to generate a calibration-corrected non-reference image frame.

10. The electronic device of claim 9, the at least one memory further storing instructions that, when executed by the at least one processor, cause the at least one processor to blend the reference image frame and the calibration-corrected non-reference image frame to generate an output image of a scene.

11. The electronic device of claim 9, wherein: the reference image frame is associated with a first exposure duration; and the non-reference image frame is associated with a second exposure duration that is shorter than the first exposure duration.

12. The electronic device of claim 9, wherein the instructions that when executed cause the at least one processor to generate the mask comprise: instructions that when executed cause the at least one processor to: generate a reference mask based on the reference image frame and a reference luma threshold; generate a non-reference mask based on the non-reference image frame and a non-reference luma threshold; and determine an intersection of the reference mask and the non-reference mask.

13. The electronic device of claim 9, wherein the instructions that when executed cause the at least one processor to determine the scaling coefficient and the offset coefficient for each of the color channels of the non-reference image frame comprise: instructions that when executed cause the at least one processor to: identify pairs of pixels based on the mask, each pair of pixels including one of the pixels of the reference image frame and one of the pixels of the non-reference image frame; fit a noisy model to the pairs of pixels; and use an objective function that includes the model to determine the scaling coefficients and the offset coefficients.

14. The electronic device of claim 9, the at least one memory further storing instructions that, when executed by the at least one processor, cause the at least one processor to: detect a saturation area of the non-reference image frame; and blend the detected saturation area into the calibration-corrected non-reference image frame.

15. The electronic device of claim 14, the at least one memory further storing instructions that, when executed by the at least one processor, cause the at least one processor to: remove lens-shading corrected (LSC) data from at least one of the reference image frame or the non-reference image frame, the mask based on the reference image frame and the non-reference image frame that

- do not contain the LSC data; and re-apply the LSC data to the calibration-corrected non-reference image frame prior to blending the detected saturation area into the calibration-corrected non-reference image frame.
16. The electronic device of claim 14, wherein: the instructions that when executed cause the at least one processor to detect the saturation area comprise: instructions that when executed cause the at least one processor to suppress a highest value among the color channels at each pixel location in the non-reference image frame and generate a saturation map; and the instructions that when executed cause the at least one processor to blend the detected saturation area into the calibration-corrected non-reference image frame comprise: instructions that when executed cause the at least one processor to blend the non-reference image frame and the calibration-corrected non-reference image frame based on the saturation map.
17. A non-transitory machine readable medium containing instructions that when executed cause at least one processor to: obtain a reference image frame and a non-reference image frame; generate a mask based on the reference image frame and the non-reference image frame; determine a scaling coefficient and an offset coefficient for each of multiple color channels of the non-reference image frame based on pixels in the reference image frame and pixels in the non-reference image frame that are identified by the mask; and apply the scaling and offset coefficients to the non-reference image frame in order to generate a calibration-corrected non-reference image frame.
18. The non-transitory machine readable medium of claim 17, wherein the instructions that when executed cause the at least one processor to generate the mask comprise: instructions that when executed cause the at least one processor to: generate a reference mask based on the reference image frame and a reference luma threshold; generate a non-reference mask based on the non-reference image frame and a non-reference luma threshold; and determine an intersection of the reference mask and the non-reference mask.
19. The non-transitory machine readable medium of claim 17, wherein the instructions that when executed cause the at least one processor to determine the scaling coefficient and the offset coefficient for each of the color channels of the non-reference image frame comprise: instructions that when executed cause the at least one processor to: identify pairs of pixels based on the mask, each pair of pixels including one of the pixels of the reference image frame and one of the pixels of the non-reference image frame; fit a noisy model to the pairs of pixels; and use an objective function that includes the model to determine the scaling coefficients and the offset coefficients.
20. The non-transitory machine readable medium of claim 17, further containing instructions that when executed cause the at least one processor to: detect a saturation area of the non-reference image frame; and blend the detected saturation area into the calibration-corrected non-reference image frame.
-