

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250284388

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

Gray; Patrick Troy et al.

Single User or Few Users Identification and Blocking Operable Touch Sensor Device

Abstract

A touch sensor system includes touch sensors, drive-sense circuits (DSCs), memory, and a processing module. A DSC drives a first signal via a single line coupling to a touch sensor and simultaneously senses, when present, a second signal that is uniquely associated with a user. The DSC processes the first signal and/or the second signal to generate a digital signal that is representative of an electrical characteristic of the touch sensor. The processing module executes operational instructions (stored in the memory) to process the digital signal to detect interaction of the user with the touch sensor and to determine whether the interaction of the user with the touch sensor compares favorably with authorization. When not authorized, the processing module aborts execution of operation(s) associated with the interaction of the user with the touch sensor. Alternatively, when authorized, the processing module facilitates execution of the operation(s).

Inventors: Gray; Patrick Troy (Cedar Park, TX), Morrison; Gerald Dale (Redmond, WA), Van Ostrand; Daniel Keith (Leander, TX), Seger, JR.; Richard Stuart (Belton, TX)

Applicant: SIGMASENSE, LLC. (Austin, TX)

Family ID: 1000008618178

Assignee: SIGMASENSE, LLC. (Austin, TX)

Appl. No.: 19/173952

Filed: April 09, 2025

Related U.S. Application Data

parent US continuation 18238582 20230828 parent-grant-document US 12277312 child US 19173952

parent US continuation 17591058 20220202 parent-grant-document US 11740781 child US 18238582

parent US continuation 17082616 20201028 parent-grant-document US 11269510 child US 17591058
parent US continuation 16131990 20180914 parent-grant-document US 10845985 child US 17082616

Publication Classification

Int. Cl.: G06F3/0488 (20220101); G06F3/041 (20060101); G06F3/044 (20060101)

U.S. Cl.:

CPC G06F3/0488 (20130101); G06F3/0412 (20130101); G06F3/044 (20130101);

Background/Summary

CROSS REFERENCE TO RELATED PATENTS [0001] The present U.S. Utility Patent Application claims priority pursuant to 35 U.S.C. § 120 as a continuation of U.S. Utility application Ser. No. 18/238,582, entitled “SINGLE USER OR FEW USERS IDENTIFICATION AND BLOCKING OPERABLE TOUCH SENSOR DEVICE,” filed Aug. 28, 2023, pending, and scheduled to issue as U.S. Pat. No. 12,277,312 on Apr. 15, 2025, which is a continuation of U.S. Utility application Ser. No. 17/591,058, entitled “SINGLE USER OR FEW USERS IDENTIFICATION AND BLOCKING OPERABLE TOUCH SENSOR DEVICE,” filed Feb. 2, 2022, now issued as U.S. Pat. No. 11,740,781 on Aug. 29, 2023, which claims priority pursuant to 35 U.S.C. § 120 as a continuation of U.S. Utility application Ser. No. 17/082,616, entitled “IDENTIFICATION IN TOUCH SYSTEMS,” filed Oct. 28, 2020, now issued as U.S. Pat. No. 11,269,510 on Mar. 8, 2022, which claims priority pursuant to 35 U.S.C. § 120 as a continuation of U.S. Utility application Ser. No. 16/131,990, entitled “IDENTIFICATION IN TOUCH SYSTEMS,” filed Sep. 14, 2018, now issued as U.S. Pat. No. 10,845,985 on Nov. 24, 2020, all of which are hereby incorporated herein by reference in their entirety and made part of the present U.S. Utility Patent Application for all purposes.

STATEMENT REGARDING FEDERALLY SPONSORED RESEARCH OR DEVELOPMENT [0002] Not Applicable.

INCORPORATION-BY-REFERENCE OF MATERIAL SUBMITTED ON A COMPACT DISC [0003] Not Applicable.

BACKGROUND OF THE INVENTION

Technical Field of the Invention

[0004] This invention relates generally to data communication systems and more particularly to sensed data collection and/or communication.

Description of Related Art

[0005] Sensors are used in a wide variety of applications ranging from in-home automation, to industrial systems, to health care, to transportation, and so on. For example, sensors are placed in bodies, automobiles, airplanes, boats, ships, trucks, motorcycles, cell phones, televisions, touch-screens, industrial plants, appliances, motors, checkout counters, etc. for the variety of applications.

[0006] In general, a sensor converts a physical quantity into an electrical or optical signal. For example, a sensor converts a physical phenomenon, such as a biological condition, a chemical condition, an electric condition, an electromagnetic condition, a temperature, a magnetic condition, mechanical motion (position, velocity, acceleration, force, pressure), an optical condition, and/or a radioactivity condition, into an electrical signal.

[0007] A sensor includes a transducer, which functions to convert one form of energy (e.g., force) into another form of energy (e.g., electrical signal). There are a variety of transducers to support the various applications of sensors. For example, a transducer is capacitor, a piezoelectric transducer, a piezoresistive transducer, a thermal transducer, a thermal-couple, a photoconductive transducer such as a photoresistor, a photodiode, and/or phototransistor.

[0008] A sensor circuit is coupled to a sensor to provide the sensor with power and to receive the signal representing the physical phenomenon from the sensor. The sensor circuit includes at least three electrical connections to the sensor: one for a power supply; another for a common voltage reference (e.g., ground); and a third for receiving the signal representing the physical phenomenon. The signal representing the physical phenomenon will vary from the power supply voltage to ground as the physical phenomenon changes from one extreme to another (for the range of sensing the physical phenomenon).

[0009] The sensor circuits provide the received sensor signals to one or more computing devices for processing. A computing device is known to communicate data, process data, and/or store data. The computing device may be a cellular phone, a laptop, a tablet, a personal computer (PC), a work station, a video game device, a server, and/or a data center that support millions of web searches, stock trades, or on-line purchases every hour.

[0010] The computing device processes the sensor signals for a variety of applications. For example, the computing device processes sensor signals to determine temperatures of a variety of items in a refrigerated truck during transit. As another example, the computing device processes the sensor signals to determine a touch on a touch screen. As yet another example, the computing device processes the sensor signals to determine various data points in a production line of a product.

Description

BRIEF DESCRIPTION OF THE SEVERAL VIEWS OF THE DRAWING(S)

[0011] FIG. 1 is a schematic block diagram of an embodiment of a communication system in accordance with the present invention;

[0012] FIG. 2 is a schematic block diagram of an embodiment of a computing device in accordance with the present invention;

[0013] FIG. 3 is a schematic block diagram of another embodiment of a computing device in accordance with the present invention;

[0014] FIG. 4 is a schematic block diagram of another embodiment of a computing device in accordance with the present invention;

[0015] FIG. 5A is a schematic plot diagram of a computing subsystem in accordance with the present invention;

[0016] FIG. 5B is a schematic block diagram of another embodiment of a computing subsystem in accordance with the present invention;

[0017] FIG. 5C is a schematic block diagram of another embodiment of a computing subsystem in accordance with the present invention;

[0018] FIG. 5D is a schematic block diagram of another embodiment of a computing subsystem in accordance with the present invention;

[0019] FIG. 5E is a schematic block diagram of another embodiment of a computing subsystem in accordance with the present invention;

[0020] FIG. 6 is a schematic block diagram of a drive center circuit in accordance with the present invention;

[0021] FIG. 6A is a schematic block diagram of another embodiment of a drive sense circuit in accordance with the present invention;

[0022] FIG. **7** is an example of a power signal graph in accordance with the present invention;
[0023] FIG. **8** is an example of a sensor graph in accordance with the present invention;
[0024] FIG. **9** is a schematic block diagram of another example of a power signal graph in accordance with the present invention;
[0025] FIG. **10** is a schematic block diagram of another example of a power signal graph in accordance with the present invention;
[0026] FIG. **11** is a schematic block diagram of another example of a power signal graph in accordance with the present invention;
[0027] FIG. **11A** is a schematic block diagram of another example of a power signal graph in accordance with the present invention;
[0028] FIG. **12** is a schematic block diagram of an embodiment of a power signal change detection circuit in accordance with the present invention;
[0029] FIG. **13** is a schematic block diagram of another embodiment of a drive-sense circuit in accordance with the present invention;
[0030] FIG. **14** is a schematic block diagram of an embodiment of a user identification capable touch sensor implemented with e-pens in accordance with the present invention;
[0031] FIG. **15** is a schematic block diagram of an embodiment of a user identification capable touch sensor implemented with conductive mats associated with users in accordance with the present invention;
[0032] FIG. **16** is a schematic block diagram of an embodiment of a user identification capable touch sensor implemented with seats associated with users in accordance with the present invention;
[0033] FIG. **17** is a schematic block diagram of an embodiment of a user identification capable touch sensor implemented with drive-sense circuit interfaces associated with users in accordance with the present invention;
[0034] FIG. **18** is a schematic block diagram of an embodiment of a user identification capable touch sensor implemented within an automobile in accordance with the present invention;
[0035] FIG. **19** is a schematic block diagram of another embodiment of a user identification capable touch sensor implemented within an automobile in accordance with the present invention;
[0036] FIG. **20** is a schematic block diagram of an embodiment of a user identification capable touch sensor in accordance with the present invention;
[0037] FIG. **21** is a schematic block diagram of another embodiment of a user identification capable touch sensor in accordance with the present invention;
[0038] FIG. **22** is a schematic block diagram of an embodiment of a method for execution by one or more devices in accordance with the present invention;
[0039] FIG. **23** is a schematic block diagram of another embodiment of a method for execution by one or more devices in accordance with the present invention;
[0040] FIG. **24** is a schematic block diagram of an embodiment of a portion of a touch sensor that includes two touch sensors in accordance with the present invention;
[0041] FIG. **25** is a schematic block diagram of an embodiment of a touch sensor that includes three touch sensors in accordance with the present invention;
[0042] FIG. **26** is a schematic block diagram of an embodiment of a that includes n touch sensors in accordance with the present invention, where n is a positive integer greater than or equal to 3;
[0043] FIG. **27** is a schematic block diagram of an embodiment of a touch sensor system in accordance with the present invention;
[0044] FIG. **28** is a schematic block diagram of another embodiment of a touch sensor system in accordance with the present invention;
[0045] FIG. **29A** is a schematic block diagram of another embodiment of a method for execution by one or more devices in accordance with the present invention;
[0046] FIG. **29B** is a schematic block diagram of another embodiment of a method for execution

by one or more devices in accordance with the present invention;

[0047] FIG. **30A** is a schematic block diagram of another embodiment of a method for execution by one or more devices in accordance with the present invention;

[0048] FIG. **30B** is a schematic block diagram of another embodiment of a method for execution by one or more devices in accordance with the present invention;

[0049] FIG. **31** is a schematic block diagram of another embodiment of a method for execution by one or more devices in accordance with the present invention;

[0050] FIG. **32** is a schematic block diagram of an embodiment of a vehicle implemented with user-interactive glass feature in accordance with the present invention;

[0051] FIG. **33** is a schematic block diagram of an embodiment of a shower stall implemented with user-interactive glass feature in accordance with the present invention;

[0052] FIG. **34** is a schematic block diagram of an embodiment of a user-interactive glass feature implemented with one or more identifiers in accordance with the present invention;

[0053] FIG. **35** is a schematic block diagram of an embodiment of a steering wheel implemented with a touch sensor in accordance with the present invention;

[0054] FIG. **36** is a schematic block diagram of another embodiment of a steering wheel implemented with a touch sensor in accordance with the present invention;

[0055] FIG. **37** is a schematic block diagram of an embodiment of a field of view user-interactive glass feature in accordance with the present invention;

[0056] FIG. **38** is a schematic block diagram of another embodiment of a field of view user-interactive glass feature in accordance with the present invention;

[0057] FIG. **39** is a schematic block diagram of another embodiment of a field of view user-interactive glass feature in accordance with the present invention;

[0058] FIG. **40** is a schematic block diagram of another embodiment of a field of view user-interactive glass feature in accordance with the present invention;

[0059] FIG. **41** is a schematic block diagram of an embodiment of another embodiment of a method for execution by one or more devices in accordance with the present invention;

[0060] FIG. **42** is a schematic block diagram of an embodiment of a touchscreen implemented with an external controller in accordance with the present invention;

[0061] FIG. **43** is a schematic block diagram of various embodiment of touchscreens implemented with external controllers in accordance with the present invention;

[0062] FIG. **44** is a schematic block diagram of an embodiment of a touchscreen implemented with one or more touch sensors implemented in touchscreen's bezel the in accordance with the present invention;

[0063] FIG. **45** is a schematic block diagram of an embodiment of another embodiment of a method for execution by one or more devices in accordance with the present invention;

[0064] FIG. **46** is a schematic block diagram of an embodiment of another embodiment of a method for execution by one or more devices in accordance with the present invention;

[0065] FIG. **47** is a schematic block diagram of an embodiment of a radial tire in accordance with the present invention;

[0066] FIG. **48** is a schematic block diagram of an embodiment of a various degrees of inflation of a tire in accordance with the present invention;

[0067] FIG. **49** is a schematic block diagram of an embodiment of a tire monitoring system in accordance with the present invention;

[0068] FIG. **50** is a schematic block diagram of another embodiment of a tire monitoring system in accordance with the present invention;

[0069] FIG. **51** is a schematic block diagram of an embodiment of tire profile monitoring in accordance with the present invention;

[0070] FIG. **52** is a schematic block diagram of another embodiment of a tire monitoring system in accordance with the present invention;

[0071] FIG. 53 is a schematic block diagram of another embodiment of a tire monitoring system in accordance with the present invention; and

[0072] FIG. 54 is a schematic block diagram of another embodiment of a tire monitoring system in accordance with the present invention.

DETAILED DESCRIPTION OF THE INVENTION

[0073] FIG. 1 is a schematic block diagram of an embodiment of a communication system **10** that includes a plurality of computing devices **12-10**, one or more servers **22**, one or more databases **24**, one or more networks **26**, a plurality of drive-sense circuits **28**, a plurality of sensors **30**, and a plurality of actuators **32**. Computing devices **14** include a touch screen **16** with sensors and drive-sensor circuits and computing devices **18** include a touch & tactic screen **20** that includes sensors, actuators, and drive-sense circuits.

[0074] A sensor **30** functions to convert a physical input into an electrical output and/or an optical output. The physical input of a sensor may be one of a variety of physical input conditions. For example, the physical condition includes one or more of, but is not limited to, acoustic waves (e.g., amplitude, phase, polarization, spectrum, and/or wave velocity); a biological and/or chemical condition (e.g., fluid concentration, level, composition, etc.); an electric condition (e.g., charge, voltage, current, conductivity, permittivity, eclectic field, which includes amplitude, phase, and/or polarization); a magnetic condition (e.g., flux, permeability, magnetic field, which amplitude, phase, and/or polarization); an optical condition (e.g., refractive index, reflectivity, absorption, etc.); a thermal condition (e.g., temperature, flux, specific heat, thermal conductivity, etc.); and a mechanical condition (e.g., position, velocity, acceleration, force, strain, stress, pressure, torque, etc.). For example, piezoelectric sensor converts force or pressure into an eclectic signal. As another example, a microphone converts audible acoustic waves into electrical signals.

[0075] There are a variety of types of sensors to sense the various types of physical conditions. Sensor types include, but are not limited to, capacitor sensors, inductive sensors, accelerometers, piezoelectric sensors, light sensors, magnetic field sensors, ultrasonic sensors, temperature sensors, infrared (IR) sensors, touch sensors, proximity sensors, pressure sensors, level sensors, smoke sensors, and gas sensors. In many ways, sensors function as the interface between the physical world and the digital world by converting real world conditions into digital signals that are then processed by computing devices for a vast number of applications including, but not limited to, medical applications, production automation applications, home environment control, public safety, and so on.

[0076] The various types of sensors have a variety of sensor characteristics that are factors in providing power to the sensors, receiving signals from the sensors, and/or interpreting the signals from the sensors. The sensor characteristics include resistance, reactance, power requirements, sensitivity, range, stability, repeatability, linearity, error, response time, and/or frequency response. For example, the resistance, reactance, and/or power requirements are factors in determining drive circuit requirements. As another example, sensitivity, stability, and/or linear are factors for interpreting the measure of the physical condition based on the received electrical and/or optical signal (e.g., measure of temperature, pressure, etc.).

[0077] An actuator **32** converts an electrical input into a physical output. The physical output of an actuator may be one of a variety of physical output conditions. For example, the physical output condition includes one or more of, but is not limited to, acoustic waves (e.g., amplitude, phase, polarization, spectrum, and/or wave velocity); a magnetic condition (e.g., flux, permeability, magnetic field, which amplitude, phase, and/or polarization); a thermal condition (e.g., temperature, flux, specific heat, thermal conductivity, etc.); and a mechanical condition (e.g., position, velocity, acceleration, force, strain, stress, pressure, torque, etc.). As an example, a piezoelectric actuator converts voltage into force or pressure. As another example, a speaker converts electrical signals into audible acoustic waves.

[0078] An actuator **32** may be one of a variety of actuators. For example, an actuator **32** is one of a

comb drive, a digital micro-mirror device, an electric motor, an electroactive polymer, a hydraulic cylinder, a piezoelectric actuator, a pneumatic actuator, a screw jack, a servomechanism, a solenoid, a stepper motor, a shape-memory alloy, a thermal bimorph, and a hydraulic actuator. [0079] The various types of actuators have a variety of actuator characteristics that are factors in providing power to the actuator and sending signals to the actuators for desired performance. The actuator characteristics include resistance, reactance, power requirements, sensitivity, range, stability, repeatability, linearity, error, response time, and/or frequency response. For example, the resistance, reactance, and power requirements are factors in determining drive circuit requirements. As another example, sensitivity, stability, and/or linearity are factors for generating the signaling to send to the actuator to obtain the desired physical output condition.

[0080] The computing devices **12**, **14**, and **18** may each be a portable computing device and/or a fixed computing device. A portable computing device may be a social networking device, a gaming device, a cell phone, a smart phone, a digital assistant, a digital music player, a digital video player, a laptop computer, a handheld computer, a tablet, a video game controller, and/or any other portable device that includes a computing core. A fixed computing device may be a computer (PC), a computer server, a cable set-top box, a satellite receiver, a television set, a printer, a fax machine, home entertainment equipment, a video game console, and/or any type of home or office computing equipment. The computing devices **12**, **14**, and **18** will be discussed in greater detail with reference to one or more of FIGS. 2-4.

[0081] A server **22** is a special type of computing device that is optimized for processing large amounts of data requests in parallel. A server **22** includes similar components to that of the computing devices **12**, **14**, and/or **18** with more robust processing modules, more main memory, and/or more hard drive memory (e.g., solid state, hard drives, etc.). Further, a server **22** is typically accessed remotely; as such it does not generally include user input devices and/or user output devices. In addition, a server may be a standalone separate computing device and/or may be a cloud computing device.

[0082] A database **24** is a special type of computing device that is optimized for large scale data storage and retrieval. A database **24** includes similar components to that of the computing devices **12**, **14**, and/or **18** with more hard drive memory (e.g., solid state, hard drives, etc.) and potentially with more processing modules and/or main memory. Further, a database **24** is typically accessed remotely; as such it does not generally include user input devices and/or user output devices. In addition, a database **24** may be a standalone separate computing device and/or may be a cloud computing device.

[0083] The network **26** includes one or more local area networks (LAN) and/or one or more wide area networks (WAN), which may be a public network and/or a private network. A LAN may be a wireless-LAN (e.g., Wi-Fi access point, Bluetooth, ZigBee, etc.) and/or a wired network (e.g., Firewire, Ethernet, etc.). A WAN may be a wired and/or wireless WAN. For example, a LAN may be a personal home or business's wireless network and a WAN is the Internet, cellular telephone infrastructure, and/or satellite communication infrastructure.

[0084] In an example of operation, computing device **12-1** communicates with a plurality of drive-sense circuits **28**, which, in turn, communicate with a plurality of sensors **30**. The sensors **30** and/or the drive-sense circuits **28** are within the computing device **12-1** and/or external to it. For example, the sensors **30** may be external to the computing device **12-1** and the drive-sense circuits are within the computing device **12-1**. As another example, both the sensors **30** and the drive-sense circuits **28** are external to the computing device **12-1**. When the drive-sense circuits **28** are external to the computing device, they are coupled to the computing device **12-1** via wired and/or wireless communication links as will be discussed in greater detail with reference to one or more of FIGS. 5A-5C.

[0085] The computing device **12-1** communicates with the drive-sense circuits **28** to; (a) turn them on, (b) obtain data from the sensors (individually and/or collectively), (c) instruct the drive sense

circuit on how to communicate the sensed data to the computing device **12-1**, (d) provide signaling attributes (e.g., DC level, AC level, frequency, power level, regulated current signal, regulated voltage signal, regulation of an impedance, frequency patterns for various sensors, different frequencies for different sensing applications, etc.) to use with the sensors, and/or (e) provide other commands and/or instructions.

[0086] As a specific example, the sensors **30** are distributed along a pipeline to measure flow rate and/or pressure within a section of the pipeline. The drive-sense circuits **28** have their own power source (e.g., battery, power supply, etc.) and are proximally located to their respective sensors **30**. At desired time intervals (milliseconds, seconds, minutes, hours, etc.), the drive-sense circuits **28** provide a regulated source signal or a power signal to the sensors **30**. An electrical characteristic of the sensor **30** affects the regulated source signal or power signal, which is reflective of the condition (e.g., the flow rate and/or the pressure) that sensor is sensing.

[0087] The drive-sense circuits **28** detect the effects on the regulated source signal or power signals as a result of the electrical characteristics of the sensors. The drive-sense circuits **28** then generate signals representative of change to the regulated source signal or power signal based on the detected effects on the power signals. The changes to the regulated source signals or power signals are representative of the conditions being sensed by the sensors **30**.

[0088] The drive-sense circuits **28** provide the representative signals of the conditions to the computing device **12-1**. A representative signal may be an analog signal or a digital signal. In either case, the computing device **12-1** interprets the representative signals to determine the pressure and/or flow rate at each sensor location along the pipeline. The computing device may then provide this information to the server **22**, the database **24**, and/or to another computing device for storing and/or further processing.

[0089] As another example of operation, computing device **12-2** is coupled to a drive-sense circuit **28**, which is, in turn, coupled to a sensor **30**. The sensor **30** and/or the drive-sense circuit **28** may be internal and/or external to the computing device **12-2**. In this example, the sensor **30** is sensing a condition that is particular to the computing device **12-2**. For example, the sensor **30** may be a temperature sensor, an ambient light sensor, an ambient noise sensor, etc. As described above, when instructed by the computing device **12-2** (which may be a default setting for continuous sensing or at regular intervals), the drive-sense circuit **28** provides the regulated source signal or power signal to the sensor **30** and detects an effect to the regulated source signal or power signal based on an electrical characteristic of the sensor. The drive-sense circuit generates a representative signal of the affect and sends it to the computing device **12-2**.

[0090] In another example of operation, computing device **12-3** is coupled to a plurality of drive-sense circuits **28** that are coupled to a plurality of sensors **30** and is coupled to a plurality of drive-sense circuits **28** that are coupled to a plurality of actuators **32**. The generally functionality of the drive-sense circuits **28** coupled to the sensors **30** in accordance with the above description.

[0091] Since an actuator **32** is essentially an inverse of a sensor in that an actuator converts an electrical signal into a physical condition, while a sensor converts a physical condition into an electrical signal, the drive-sense circuits **28** can be used to power actuators **32**. Thus, in this example, the computing device **12-3** provides actuation signals to the drive-sense circuits **28** for the actuators **32**. The drive-sense circuits modulate the actuation signals on to power signals or regulated control signals, which are provided to the actuators **32**. The actuators **32** are powered from the power signals or regulated control signals and produce the desired physical condition from the modulated actuation signals.

[0092] As another example of operation, computing device **12-x** is coupled to a drive-sense circuit **28** that is coupled to a sensor **30** and is coupled to a drive-sense circuit **28** that is coupled to an actuator **32**. In this example, the sensor **30** and the actuator **32** are for use by the computing device **12-x**. For example, the sensor **30** may be a piezoelectric microphone and the actuator **32** may be a piezoelectric speaker.

[0093] FIG. 2 is a schematic block diagram of an embodiment of a computing device **12** (e.g., any one of **12-1** through **12-x**). The computing device **12** includes a core control module **40**, one or more processing modules **42**, one or more main memories **44**, cache memory **46**, a video graphics processing module **48**, a display **50**, an Input-Output (I/O) peripheral control module **52**, one or more input interface modules **56**, one or more output interface modules **58**, one or more network interface modules **60**, and one or more memory interface modules **62**. A processing module **42** is described in greater detail at the end of the detailed description of the invention section and, in an alternative embodiment, has a direction connection to the main memory **44**. In an alternate embodiment, the core control module **40** and the I/O and/or peripheral control module **52** are one module, such as a chipset, a quick path interconnect (QPI), and/or an ultra-path interconnect (UPI).

[0094] Each of the main memories **44** includes one or more Random Access Memory (RAM) integrated circuits, or chips. For example, a main memory **44** includes four DDR4 (4th generation of double data rate) RAM chips, each running at a rate of 2,400 MHz. In general, the main memory **44** stores data and operational instructions most relevant for the processing module **42**. For example, the core control module **40** coordinates the transfer of data and/or operational instructions from the main memory **44** and the memory **64-66**. The data and/or operational instructions retrieve from memory **64-66** are the data and/or operational instructions requested by the processing module or will most likely be needed by the processing module. When the processing module is done with the data and/or operational instructions in main memory, the core control module **40** coordinates sending updated data to the memory **64-66** for storage.

[0095] The memory **64-66** includes one or more hard drives, one or more solid state memory chips, and/or one or more other large capacity storage devices that, in comparison to cache memory and main memory devices, is/are relatively inexpensive with respect to cost per amount of data stored. The memory **64-66** is coupled to the core control module **40** via the I/O and/or peripheral control module **52** and via one or more memory interface modules **62**. In an embodiment, the I/O and/or peripheral control module **52** includes one or more Peripheral Component Interface (PCI) buses to which peripheral components connect to the core control module **40**. A memory interface module **62** includes a software driver and a hardware connector for coupling a memory device to the I/O and/or peripheral control module **52**. For example, a memory interface **62** is in accordance with a Serial Advanced Technology Attachment (SATA) port.

[0096] The core control module **40** coordinates data communications between the processing module(s) **42** and the network(s) **26** via the I/O and/or peripheral control module **52**, the network interface module(s) **60**, and a network card **68** or **70**. A network card **68** or **70** includes a wireless communication unit or a wired communication unit. A wireless communication unit includes a wireless local area network (WLAN) communication device, a cellular communication device, a Bluetooth device, and/or a ZigBee communication device. A wired communication unit includes a Gigabit LAN connection, a Firewire connection, and/or a proprietary computer wired connection. A network interface module **60** includes a software driver and a hardware connector for coupling the network card to the I/O and/or peripheral control module **52**. For example, the network interface module **60** is in accordance with one or more versions of IEEE 802.11, cellular telephone protocols, 10/100/1000 Gigabit LAN protocols, etc.

[0097] The core control module **40** coordinates data communications between the processing module(s) **42** and input device(s) **72** via the input interface module(s) **56** and the I/O and/or peripheral control module **52**. An input device **72** includes a keypad, a keyboard, control switches, a touchpad, a microphone, a camera, etc. An input interface module **56** includes a software driver and a hardware connector for coupling an input device to the I/O and/or peripheral control module **52**. In an embodiment, an input interface module **56** is in accordance with one or more Universal Serial Bus (USB) protocols.

[0098] The core control module **40** coordinates data communications between the processing module(s) **42** and output device(s) **74** via the output interface module(s) **58** and the I/O and/or

peripheral control module **52**. An output device **74** includes a speaker, etc. An output interface module **58** includes a software driver and a hardware connector for coupling an output device to the I/O and/or peripheral control module **52**. In an embodiment, an output interface module **56** is in accordance with one or more audio codec protocols.

[0099] The processing module **42** communicates directly with a video graphics processing module **48** to display data on the display **50**. The display **50** includes an LED (light emitting diode) display, an LCD (liquid crystal display), and/or other type of display technology. The display has a resolution, an aspect ratio, and other features that affect the quality of the display. The video graphics processing module **48** receives data from the processing module **42**, processes the data to produce rendered data in accordance with the characteristics of the display, and provides the rendered data to the display **50**.

[0100] FIG. **2** further illustrates sensors **30** and actuators **32** coupled to drive-sense circuits **28**, which are coupled to the input interface module **56** (e.g., USB port). Alternatively, one or more of the drive-sense circuits **28** is coupled to the computing device via a wireless network card (e.g., WLAN) or a wired network card (e.g., Gigabit LAN). While not shown, the computing device **12** further includes a BIOS (Basic Input Output System) memory coupled to the core control module **40**.

[0101] FIG. **3** is a schematic block diagram of another embodiment of a computing device **14** that includes a core control module **40**, one or more processing modules **42**, one or more main memories **44**, cache memory **46**, a video graphics processing module **48**, a touch screen **16**, an Input-Output (I/O) peripheral control module **52**, one or more input interface modules **56**, one or more output interface modules **58**, one or more network interface modules **60**, and one or more memory interface modules **62**. The touch screen **16** includes a touch screen display **80**, a plurality of sensors **30**, a plurality of drive-sense circuits (DSC), and a touch screen processing module **82**.

[0102] Computing device **14** operates similarly to computing device **12** of FIG. **2** with the addition of a touch screen as an input device. The touch screen includes a plurality of sensors (e.g., electrodes, capacitor sensing cells, capacitor sensors, inductive sensor, etc.) to detect a proximal touch of the screen. For example, when one or more fingers touches the screen, capacitance of sensors proximal to the touch(es) are affected (e.g., impedance changes). The drive-sense circuits (DSC) coupled to the affected sensors detect the change and provide a representation of the change to the touch screen processing module **82**, which may be a separate processing module or integrated into the processing module **42**.

[0103] The touch screen processing module **82** processes the representative signals from the drive-sense circuits (DSC) to determine the location of the touch(es). This information is inputted to the processing module **42** for processing as an input. For example, a touch represents a selection of a button on screen, a scroll function, a zoom in-out function, etc.

[0104] FIG. **4** is a schematic block diagram of another embodiment of a computing device **18** that includes a core control module **40**, one or more processing modules **42**, one or more main memories **44**, cache memory **46**, a video graphics processing module **48**, a touch and tactile screen **20**, an Input-Output (I/O) peripheral control module **52**, one or more input interface modules **56**, one or more output interface modules **58**, one or more network interface modules **60**, and one or more memory interface modules **62**. The touch and tactile screen **20** includes a touch and tactile screen display **90**, a plurality of sensors **30**, a plurality of actuators **32**, a plurality of drive-sense circuits (DSC), a touch screen processing module **82**, and a tactile screen processing module **92**.

[0105] Computing device **18** operates similarly to computing device **14** of FIG. **3** with the addition of a tactile aspect to the screen **20** as an output device. The tactile portion of the screen **20** includes the plurality of actuators (e.g., piezoelectric transducers to create vibrations, solenoids to create movement, etc.) to provide a tactile feel to the screen **20**. To do so, the processing module creates tactile data, which is provided to the appropriate drive-sense circuits (DSC) via the tactile screen processing module **92**, which may be a stand-alone processing module or integrated into processing

module **42**. The drive-sense circuits (DSC) convert the tactile data into drive-actuate signals and provide them to the appropriate actuators to create the desired tactile feel on the screen **20**.

[0106] FIG. 5A is a schematic plot diagram of a computing subsystem **25** that includes a sensed data processing module **65**, a plurality of communication modules **61A-x**, a plurality of processing modules **42A-x**, a plurality of drive sense circuits **28**, and a plurality of sensors **1-x**, which may be sensors **30** of FIG. 1. The sensed data processing module **65** is one or more processing modules within one or more servers **22** and/or one more processing modules in one or more computing devices that are different than the computing devices in which processing modules **42A-x** reside.

[0107] A drive-sense circuit **28** (or multiple drive-sense circuits), a processing module (e.g., **41A**), and a communication module (e.g., **61A**) are within a common computing device. Each grouping of a drive-sense circuit(s), processing module, and communication module is in a separate computing device. A communication module **61A-x** is constructed in accordance with one or more wired communication protocol and/or one or more wireless communication protocols that is/are in accordance with the one or more of the Open System Interconnection (OSI) model, the Transmission Control Protocol/Internet Protocol (TCP/IP) model, and other communication protocol module.

[0108] In an example of operation, a processing module (e.g., **42A**) provides a control signal to its corresponding drive-sense circuit **28**. The processing module **42A** may generate the control signal, receive it from the sensed data processing module **65**, or receive an indication from the sensed data processing module **65** to generate the control signal. The control signal enables the drive-sense circuit **28** to provide a drive signal to its corresponding sensor. The control signal may further include a reference signal having one or more frequency components to facilitate creation of the drive signal and/or interpreting a sensed signal received from the sensor.

[0109] Based on the control signal, the drive-sense circuit **28** provides the drive signal to its corresponding sensor (e.g., **1**) on a drive & sense line. While receiving the drive signal (e.g., a power signal, a regulated source signal, etc.), the sensor senses a physical condition **1-x** (e.g., acoustic waves, a biological condition, a chemical condition, an electric condition, a magnetic condition, an optical condition, a thermal condition, and/or a mechanical condition). As a result of the physical condition, an electrical characteristic (e.g., impedance, voltage, current, capacitance, inductance, resistance, reactance, etc.) of the sensor changes, which affects the drive signal. Note that if the sensor is an optical sensor, it converts a sensed optical condition into an electrical characteristic.

[0110] The drive-sense circuit **28** detects the effect on the drive signal via the drive & sense line and processes the affect to produce a signal representative of power change, which may be an analog or digital signal. The processing module **42A** receives the signal representative of power change, interprets it, and generates a value representing the sensed physical condition. For example, if the sensor is sensing pressure, the value representing the sensed physical condition is a measure of pressure (e.g., x PSI (pounds per square inch)).

[0111] In accordance with a sensed data process function (e.g., algorithm, application, etc.), the sensed data processing module **65** gathers the values representing the sensed physical conditions from the processing modules. Since the sensors **1-x** may be the same type of sensor (e.g., a pressure sensor), may each be different sensors, or a combination thereof; the sensed physical conditions may be the same, may each be different, or a combination thereof. The sensed data processing module **65** processes the gathered values to produce one or more desired results. For example, if the computing subsystem **25** is monitoring pressure along a pipeline, the processing of the gathered values indicates that the pressures are all within normal limits or that one or more of the sensed pressures is not within normal limits.

[0112] As another example, if the computing subsystem **25** is used in a manufacturing facility, the sensors are sensing a variety of physical conditions, such as acoustic waves (e.g., for sound proofing, sound generation, ultrasound monitoring, etc.), a biological condition (e.g., a bacterial

contamination, etc.) a chemical condition (e.g., composition, gas concentration, etc.), an electric condition (e.g., current levels, voltage levels, electro-magnetic interference, etc.), a magnetic condition (e.g., induced current, magnetic field strength, magnetic field orientation, etc.), an optical condition (e.g., ambient light, infrared, etc.), a thermal condition (e.g., temperature, etc.), and/or a mechanical condition (e.g., physical position, force, pressure, acceleration, etc.).

[0113] The computing subsystem **25** may further include one or more actuators in place of one or more of the sensors and/or in addition to the sensors. When the computing subsystem **25** includes an actuator, the corresponding processing module provides an actuation control signal to the corresponding drive-sense circuit **28**. The actuation control signal enables the drive-sense circuit **28** to provide a drive signal to the actuator via a drive & actuate line (e.g., similar to the drive & sense line, but for the actuator). The drive signal includes one or more frequency components and/or amplitude components to facilitate a desired actuation of the actuator.

[0114] In addition, the computing subsystem **25** may include an actuator and sensor working in concert. For example, the sensor is sensing the physical condition of the actuator. In this example, a drive-sense circuit provides a drive signal to the actuator and another drive sense signal provides the same drive signal, or a scaled version of it, to the sensor. This allows the sensor to provide near immediate and continuous sensing of the actuator's physical condition. This further allows for the sensor to operate at a first frequency and the actuator to operate at a second frequency.

[0115] In an embodiment, the computing subsystem is a stand-alone system for a wide variety of applications (e.g., manufacturing, pipelines, testing, monitoring, security, etc.). In another embodiment, the computing subsystem **25** is one subsystem of a plurality of subsystems forming a larger system. For example, different subsystems are employed based on geographic location. As a specific example, the computing subsystem **25** is deployed in one section of a factory and another computing subsystem is deployed in another part of the factory. As another example, different subsystems are employed based function of the subsystems. As a specific example, one subsystem monitors a city's traffic light operation and another subsystem monitors the city's sewage treatment plants.

[0116] Regardless of the use and/or deployment of the computing system, the physical conditions it is sensing, and/or the physical conditions it is actuating, each sensor and each actuator (if included) is driven and sensed by a single line as opposed to separate drive and sense lines. This provides many advantages including, but not limited to, lower power requirements, better ability to drive high impedance sensors, lower line to line interference, and/or concurrent sensing functions.

[0117] FIG. 5B is a schematic block diagram of another embodiment of a computing subsystem **25** that includes a sensed data processing module **65**, a communication module **61**, a plurality of processing modules **42A-x**, a plurality of drive sense circuits **28**, and a plurality of sensors **1-x**, which may be sensors **30** of FIG. 1. The sensed data processing module **65** is one or more processing modules within one or more servers **22** and/or one more processing modules in one or more computing devices that are different than the computing device, devices, in which processing modules **42A-x** reside.

[0118] In an embodiment, the drive-sense circuits **28**, the processing modules, and the communication module are within a common computing device. For example, the computing device includes a central processing unit that includes a plurality of processing modules. The functionality and operation of the sensed data processing module **65**, the communication module **61**, the processing modules **42A-x**, the drive sense circuits **28**, and the sensors **1-x** are as discussed with reference to FIG. 5A.

[0119] FIG. 5C is a schematic block diagram of another embodiment of a computing subsystem **25** that includes a sensed data processing module **65**, a communication module **61**, a processing module **42**, a plurality of drive sense circuits **28**, and a plurality of sensors **1-x**, which may be sensors **30** of FIG. 1. The sensed data processing module **65** is one or more processing modules within one or more servers **22** and/or one more processing modules in one or more computing

devices that are different than the computing device in which the processing module **42** resides.

[0120] In an embodiment, the drive-sense circuits **28**, the processing module, and the communication module are within a common computing device. The functionality and operation of the sensed data processing module **65**, the communication module **61**, the processing module **42**, the drive sense circuits **28**, and the sensors **1-x** are as discussed with reference to FIG. 5A.

[0121] FIG. 5D is a schematic block diagram of another embodiment of a computing subsystem **25** that includes a processing module **42**, a reference signal circuit **100**, a plurality of drive sense circuits **28**, and a plurality of sensors **30**. The processing module **42** includes a drive-sense processing block **104**, a drive-sense control block **102**, and a reference control block **106**. Each block **102-106** of the processing module **42** may be implemented via separate modules of the processing module, may be a combination of software and hardware within the processing module, and/or may be field programmable modules within the processing module **42**.

[0122] In an example of operation, the drive-sense control block **104** generates one or more control signals to activate one or more of the drive-sense circuits **28**. For example, the drive-sense control block **102** generates a control signal that enables of the drive-sense circuits **28** for a given period of time (e.g., 1 second, 1 minute, etc.). As another example, the drive-sense control block **102** generates control signals to sequentially enable the drive-sense circuits **28**. As yet another example, the drive-sense control block **102** generates a series of control signals to periodically enable the drive-sense circuits **28** (e.g., enabled once every second, every minute, every hour, etc.).

[0123] Continuing with the example of operation, the reference control block **106** generates a reference control signal that it provides to the reference signal circuit **100**. The reference signal circuit **100** generates, in accordance with the control signal, one or more reference signals for the drive-sense circuits **28**. For example, the control signal is an enable signal, which, in response, the reference signal circuit **100** generates a pre-programmed reference signal that it provides to the drive-sense circuits **28**. In another example, the reference signal circuit **100** generates a unique reference signal for each of the drive-sense circuits **28**. In yet another example, the reference signal circuit **100** generates a first unique reference signal for each of the drive-sense circuits **28** in a first group and generates a second unique reference signal for each of the drive-sense circuits **28** in a second group.

[0124] The reference signal circuit **100** may be implemented in a variety of ways. For example, the reference signal circuit **100** includes a DC (direct current) voltage generator, an AC voltage generator, and a voltage combining circuit. The DC voltage generator generates a DC voltage at a first level and the AC voltage generator generates an AC voltage at a second level, which is less than or equal to the first level. The voltage combining circuit combines the DC and AC voltages to produce the reference signal. As examples, the reference signal circuit **100** generates a reference signal similar to the signals shown in FIG. 7, which will be subsequently discussed.

[0125] As another example, the reference signal circuit **100** includes a DC current generator, an AC current generator, and a current combining circuit. The DC current generator generates a DC current a first current level and the AC current generator generates an AC current at a second current level, which is less than or equal to the first current level. The current combining circuit combines the DC and AC currents to produce the reference signal.

[0126] Returning to the example of operation, the reference signal circuit **100** provides the reference signal, or signals, to the drive-sense circuits **28**. When a drive-sense circuit **28** is enabled via a control signal from the drive sense control block **102**, it provides a drive signal to its corresponding sensor **30**. As a result of a physical condition, an electrical characteristic of the sensor is changed, which affects the drive signal. Based on the detected effect on the drive signal and the reference signal, the drive-sense circuit **28** generates a signal representative of the effect on the drive signal.

[0127] The drive-sense circuit provides the signal representative of the effect on the drive signal to the drive-sense processing block **104**. The drive-sense processing block **104** processes the

representative signal to produce a sensed value **97** of the physical condition (e.g., a digital value that represents a specific temperature, a specific pressure level, etc.). The processing module **42** provides the sensed value **97** to another application running on the computing device, to another computing device, and/or to a server **22**.

[0128] FIG. 5E is a schematic block diagram of another embodiment of a computing subsystem **25** that includes a processing module **42**, a plurality of drive sense circuits **28**, and a plurality of sensors **30**. This embodiment is similar to the embodiment of FIG. 5D with the functionality of the drive-sense processing block **104**, a drive-sense control block **102**, and a reference control block **106** shown in greater detail. For instance, the drive-sense control block **102** includes individual enable/disable blocks **102-1** through **102-y**. An enable/disable block functions to enable or disable a corresponding drive-sense circuit in a manner as discussed above with reference to FIG. 5D.

[0129] The drive-sense processing block **104** includes variance determining modules **104-1a** through **y** and variance interpreting modules **104-2a** through **y**. For example, variance determining module **104-1a** receives, from the corresponding drive-sense circuit **28**, a signal representative of a physical condition sensed by a sensor. The variance determining module **104-1a** functions to determine a difference from the signal representing the sensed physical condition with a signal representing a known, or reference, physical condition. The variance interpreting module **104-1b** interprets the difference to determine a specific value for the sensed physical condition.

[0130] As a specific example, the variance determining module **104-1a** receives a digital signal of 1001 0110 (150 in decimal) that is representative of a sensed physical condition (e.g., temperature) sensed by a sensor from the corresponding drive-sense circuit **28**. With 8-bits, there are $2^{sup.8}$ (256) possible signals representing the sensed physical condition. Assume that the units for temperature is Celsius and a digital value of 0100 0000 (64 in decimal) represents the known value for 25 degree Celsius. The variance determining module **104-b1** determines the difference between the digital signal representing the sensed value (e.g., 1001 0110, 150 in decimal) and the known signal value of (e.g., 0100 0000, 64 in decimal), which is 0011 0000 (86 in decimal). The variance determining module **104-b1** then determines the sensed value based on the difference and the known value. In this example, the sensed value equals $25+86*(100/256)=25+33.6=58.6$ degrees Celsius.

[0131] FIG. 6 is a schematic block diagram of a drive center circuit **28-a** coupled to a sensor **30**. The drive sense-sense circuit **28** includes a power source circuit **110** and a power signal change detection circuit **112**. The sensor **30** includes one or more transducers that have varying electrical characteristics (e.g., capacitance, inductance, impedance, current, voltage, etc.) based on varying physical conditions **114** (e.g., pressure, temperature, biological, chemical, etc.), or vice versa (e.g., an actuator).

[0132] The power source circuit **110** is operably coupled to the sensor **30** and, when enabled (e.g., from a control signal from the processing module **42**, power is applied, a switch is closed, a reference signal is received, etc.) provides a power signal **116** to the sensor **30**. The power source circuit **110** may be a voltage supply circuit (e.g., a battery, a linear regulator, an unregulated DC-to-DC converter, etc.) to produce a voltage-based power signal, a current supply circuit (e.g., a current source circuit, a current mirror circuit, etc.) to produce a current-based power signal, or a circuit that provide a desired power level to the sensor and substantially matches impedance of the sensor. The power source circuit **110** generates the power signal **116** to include a DC (direct current) component and/or an oscillating component.

[0133] When receiving the power signal **116** and when exposed to a condition **114**, an electrical characteristic of the sensor affects **118** the power signal. When the power signal change detection circuit **112** is enabled, it detects the affect **118** on the power signal as a result of the electrical characteristic of the sensor. For example, the power signal is a 1.5 voltage signal and, under a first condition, the sensor draws 1 milliamp of current, which corresponds to an impedance of 1.5 K Ohms. Under a second conditions, the power signal remains at 1.5 volts and the current increases to

1.5 milliamps. As such, from condition 1 to condition 2, the impedance of the sensor changed from 1.5 K Ohms to 1 K Ohms. The power signal change detection circuit **112** determines this change and generates a representative signal **120** of the change to the power signal.

[0134] As another example, the power signal is a 1.5 voltage signal and, under a first condition, the sensor draws 1 milliamp of current, which corresponds to an impedance of 1.5 K Ohms. Under a second conditions, the power signal drops to 1.3 volts and the current increases to 1.3 milliamps. As such, from condition 1 to condition 2, the impedance of the sensor changed from 1.5 K Ohms to 1 K Ohms. The power signal change detection circuit **112** determines this change and generates a representative signal **120** of the change to the power signal.

[0135] The power signal **116** includes a DC component **122** and/or an oscillating component **124** as shown in FIG. 7. The oscillating component **124** includes a sinusoidal signal, a square wave signal, a triangular wave signal, a multiple level signal (e.g., has varying magnitude over time with respect to the DC component), and/or a polygonal signal (e.g., has a symmetrical or asymmetrical polygonal shape with respect to the DC component). Note that the power signal is shown without affect from the sensor as the result of a condition or changing condition.

[0136] In an embodiment, power generating circuit **110** varies frequency of the oscillating component **124** of the power signal **116** so that it can be tuned to the impedance of the sensor and/or to be off-set in frequency from other power signals in a system. For example, a capacitance sensor's impedance decreases with frequency. As such, if the frequency of the oscillating component is too high with respect to the capacitance, the capacitor looks like a short and variances in capacitances will be missed. Similarly, if the frequency of the oscillating component is too low with respect to the capacitance, the capacitor looks like an open and variances in capacitances will be missed.

[0137] In an embodiment, the power generating circuit **110** varies magnitude of the DC component **122** and/or the oscillating component **124** to improve resolution of sensing and/or to adjust power consumption of sensing. In addition, the power generating circuit **110** generates the drive signal **110** such that the magnitude of the oscillating component **124** is less than magnitude of the DC component **122**.

[0138] FIG. 6A is a schematic block diagram of a drive center circuit **28-a1** coupled to a sensor **30**. The drive sense-sense circuit **28-a1** includes a signal source circuit **111**, a signal change detection circuit **113**, and a power source **115**. The power source **115** (e.g., a battery, a power supply, a current source, etc.) generates a voltage and/or current that is combined with a signal **117**, which is produced by the signal source circuit **111**. The combined signal is supplied to the sensor **30**.

[0139] The signal source circuit **111** may be a voltage supply circuit (e.g., a battery, a linear regulator, an unregulated DC-to-DC converter, etc.) to produce a voltage-based signal **117**, a current supply circuit (e.g., a current source circuit, a current mirror circuit, etc.) to produce a current-based signal **117**, or a circuit that provide a desired power level to the sensor and substantially matches impedance of the sensor. The signal source circuit **111** generates the signal **117** to include a DC (direct current) component and/or an oscillating component.

[0140] When receiving the combined signal (e.g., signal **117** and power from the power source) and when exposed to a condition **114**, an electrical characteristic of the sensor affects **119** the signal. When the signal change detection circuit **113** is enabled, it detects the affect **119** on the signal as a result of the electrical characteristic of the sensor.

[0141] FIG. 8 is an example of a sensor graph that plots an electrical characteristic versus a condition. The sensor has a substantially linear region in which an incremental change in a condition produces a corresponding incremental change in the electrical characteristic. The graph shows two types of electrical characteristics: one that increases as the condition increases and the other that decreases and the condition increases. As an example of the first type, impedance of a temperature sensor increases and the temperature increases. As an example of a second type, a capacitance touch sensor decreases in capacitance as a touch is sensed.

[0142] FIG. **9** is a schematic block diagram of another example of a power signal graph in which the electrical characteristic or change in electrical characteristic of the sensor is affecting the power signal. In this example, the effect of the electrical characteristic or change in electrical characteristic of the sensor reduced the DC component but had little to no effect on the oscillating component. For example, the electrical characteristic is resistance. In this example, the resistance or change in resistance of the sensor decreased the power signal, inferring an increase in resistance for a relatively constant current.

[0143] FIG. **10** is a schematic block diagram of another example of a power signal graph in which the electrical characteristic or change in electrical characteristic of the sensor is affecting the power signal. In this example, the effect of the electrical characteristic or change in electrical characteristic of the sensor reduced magnitude of the oscillating component but had little to no effect on the DC component. For example, the electrical characteristic is impedance of a capacitor and/or an inductor. In this example, the impedance or change in impedance of the sensor decreased the magnitude of the oscillating signal component, inferring an increase in impedance for a relatively constant current.

[0144] FIG. **11** is a schematic block diagram of another example of a power signal graph in which the electrical characteristic or change in electrical characteristic of the sensor is affecting the power signal. In this example, the effect of the electrical characteristic or change in electrical characteristic of the sensor shifted frequency of the oscillating component but had little to no effect on the DC component. For example, the electrical characteristic is reactance of a capacitor and/or an inductor. In this example, the reactance or change in reactance of the sensor shifted frequency of the oscillating signal component, inferring an increase in reactance (e.g., sensor is functioning as an integrator or phase shift circuit).

[0145] FIG. **11A** is a schematic block diagram of another example of a power signal graph in which the electrical characteristic or change in electrical characteristic of the sensor is affecting the power signal. In this example, the effect of the electrical characteristic or change in electrical characteristic of the sensor changes the frequency of the oscillating component but had little to no effect on the DC component. For example, the sensor includes two transducers that oscillate at different frequencies. The first transducer receives the power signal at a frequency of $f_{\text{sub}.1}$ and converts it into a first physical condition. The second transducer is stimulated by the first physical condition to create an electrical signal at a different frequency $f_{\text{sub}.2}$. In this example, the first and second transducers of the sensor change the frequency of the oscillating signal component, which allows for more granular sensing and/or a broader range of sensing.

[0146] FIG. **12** is a schematic block diagram of an embodiment of a power signal change detection circuit **112** receiving the affected power signal **118** and the power signal **116** as generated to produce, therefrom, the signal representative **120** of the power signal change. The affect **118** on the power signal is the result of an electrical characteristic and/or change in the electrical characteristic of a sensor; a few examples of the affects are shown in FIGS. **8-11A**.

[0147] In an embodiment, the power signal change detection circuit **112** detect a change in the DC component **122** and/or the oscillating component **124** of the power signal **116**. The power signal change detection circuit **112** then generates the signal representative **120** of the change to the power signal based on the change to the power signal. For example, the change to the power signal results from the impedance of the sensor and/or a change in impedance of the sensor. The representative signal **120** is reflective of the change in the power signal and/or in the change in the sensor's impedance.

[0148] In an embodiment, the power signal change detection circuit **112** is operable to detect a change to the oscillating component at a frequency, which may be a phase shift, frequency change, and/or change in magnitude of the oscillating component. The power signal change detection circuit **112** is also operable to generate the signal representative of the change to the power signal based on the change to the oscillating component at the frequency. The power signal change

detection circuit **112** is further operable to provide feedback to the power source circuit **110** regarding the oscillating component. The feedback allows the power source circuit **110** to regulate the oscillating component at the desired frequency, phase, and/or magnitude.

[0149] FIG. **13** is a schematic block diagram of another embodiment of a drive sense circuit **28-b** includes a change detection circuit **150**, a regulation circuit **152**, and a power source circuit **154**. The drive-sense circuit **28-b** is coupled to the sensor **30**, which includes a transducer that has varying electrical characteristics (e.g., capacitance, inductance, impedance, current, voltage, etc.) based on varying physical conditions **114** (e.g., pressure, temperature, biological, chemical, etc.). [0150] The power source circuit **154** is operably coupled to the sensor **30** and, when enabled (e.g., from a control signal from the processing module **42**, power is applied, a switch is closed, a reference signal is received, etc.) provides a power signal **158** to the sensor **30**. The power source circuit **154** may be a voltage supply circuit (e.g., a battery, a linear regulator, an unregulated DC-to-DC converter, etc.) to produce a voltage-based power signal or a current supply circuit (e.g., a current source circuit, a current mirror circuit, etc.) to produce a current-based power signal. The power source circuit **154** generates the power signal **158** to include a DC (direct current) component and an oscillating component.

[0151] When receiving the power signal **158** and when exposed to a condition **114**, an electrical characteristic of the sensor affects **160** the power signal. When the change detection circuit **150** is enabled, it detects the affect **160** on the power signal as a result of the electrical characteristic of the sensor **30**. The change detection circuit **150** is further operable to generate a signal **120** that is representative of change to the power signal based on the detected effect on the power signal.

[0152] The regulation circuit **152**, when its enabled, generates regulation signal **156** to regulate the DC component to a desired DC level and/or regulate the oscillating component to a desired oscillating level (e.g., magnitude, phase, and/or frequency) based on the signal **120** that is representative of the change to the power signal. The power source circuit **154** utilizes the regulation signal **156** to keep the power signal at a desired setting **158** regardless of the electrical characteristic of the sensor. In this manner, the amount of regulation is indicative of the affect the electrical characteristic had on the power signal.

[0153] In an example, the power source circuit **158** is a DC-DC converter operable to provide a regulated power signal having DC and AC components. The change detection circuit **150** is a comparator and the regulation circuit **152** is a pulse width modulator to produce the regulation signal **156**. The comparator compares the power signal **158**, which is affected by the sensor, with a reference signal that includes DC and AC components. When the electrical characteristics is at a first level (e.g., a first impedance), the power signal is regulated to provide a voltage and current such that the power signal substantially resembles the reference signal.

[0154] When the electrical characteristics changes to a second level (e.g., a second impedance), the change detection circuit **150** detects a change in the DC and/or AC component of the power signal **158** and generates the representative signal **120**, which indicates the changes. The regulation circuit **152** detects the change in the representative signal **120** and creates the regulation signal to substantially remove the effect on the power signal. The regulation of the power signal **158** may be done by regulating the magnitude of the DC and/or AC components, by adjusting the frequency of AC component, and/or by adjusting the phase of the AC component.

[0155] With respect to the operation of various drive-sense circuits as described herein and/or their equivalents, note that the operation of such a drive-sense circuit is operable simultaneously to drive and sense a signal via a single line. In comparison to switched, time-divided, time-multiplexed, etc. operation in which there is switching between driving and sensing (e.g., driving at first time, sensing at second time, etc.) of different respective signals at separate and distinct times, the drive-sense circuit is operable simultaneously to perform both driving and sensing of a signal. In some examples, such simultaneous driving and sensing is performed via a single line using a drive-sense circuit.

[0156] In addition, other alternative implementations of various drive-sense circuits are described in U.S. Utility patent application Ser. No. 16/113,379, entitled “DRIVE SENSE CIRCUIT WITH DRIVE-SENSE LINE,” (Attorney Docket No. SGS00009), filed Aug. 27, 2018, now issued as U.S. Pat. No. 11,099,032 on Aug. 24, 2021. Any instantiation of a drive-sense circuit as described herein may be implemented using any of the various implementations of various drive-sense circuits described in U.S. Utility patent application Ser. No. 16/113,379.

[0157] In addition, note that the one or more signals provided from a drive-sense circuit (DSC) may be of any of a variety of types. For example, such a signal may be based on encoding of one or more bits to generate one or more coded bits used to generate modulation data (or generally, data). For example, a device is configured to perform forward error correction (FEC) and/or error checking and correction (ECC) code of one or more bits to generate one or more coded bits. Examples of FEC and/or ECC may include turbo code, convolutional code, turbo trellis coded modulation (TTCM), low density parity check (LDPC) code, Reed-Solomon (RS) code, BCH (Bose and Ray-Chaudhuri, and Hocquenghem) code, binary convolutional code (BCC), Cyclic Redundancy Check (CRC), and/or any other type of ECC and/or FEC code and/or combination thereof, etc. Note that more than one type of ECC and/or FEC code may be used in any of various implementations including concatenation (e.g., first ECC and/or FEC code followed by second ECC and/or FEC code, etc. such as based on an inner code/outer code architecture, etc.), parallel architecture (e.g., such that first ECC and/or FEC code operates on first bits while second ECC and/or FEC code operates on second bits, etc.), and/or any combination thereof.

[0158] Also, the one or more coded bits may then undergo modulation or symbol mapping to generate modulation symbols (e.g., the modulation symbols may include data intended for one or more recipient devices, components, elements, etc.). Note that such modulation symbols may be generated using any of various types of modulation coding techniques. Examples of such modulation coding techniques may include binary phase shift keying (BPSK), quadrature phase shift keying (QPSK), 8-phase shift keying (PSK), 16 quadrature amplitude modulation (QAM), 32 amplitude and phase shift keying (APSK), etc., uncoded modulation, and/or any other desired types of modulation including higher ordered modulations that may include even greater number of constellation points (e.g., 1024 QAM, etc.).

[0159] In addition, note a signal provided from a DSC may be of a unique frequency that is different from signals provided from other DSCs. Also, a signal provided from a DSC may include multiple frequencies independently or simultaneously. The frequency of the signal can be hopped on a pre-arranged pattern. In some examples, a handshake is established between one or more DSCs and one or more processing module (e.g., one or more controllers) such that the one or more DSC is/are directed by the one or more processing modules regarding which frequency or frequencies and/or which other one or more characteristics of the one or more signals to use at one or more respective times and/or in one or more particular situations.

[0160] FIG. 14 is a schematic block diagram of an embodiment 1400 of a user identification capable touch sensor implemented with e-pens (electronic-pens) in accordance with the present invention. A touch sensor system includes one or more touch sensors 1410. The one or more touch sensors 1410 may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, a film that includes any desired implementation of components to facilitate touch sensor operation, and/or any other configuration by which interaction with the touch sensor may be performed. Note that such interaction of a user with a touch sensor may correspond to the user touching the touch sensor, the user being in proximate distance to the touch sensor (e.g., within a sufficient proximity to the touch sensor that coupling from the user to the touch sensor may be performed via capacitively coupling (CC), etc. and/or generally any manner of interacting with the touch sensor that is detectable based on processing of signals transmitted to and/or sensed from the touch sensor). With respect to the various

embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types.

[0161] One example of such interaction it was with the one or more touch sensors **1410** is via capacitive coupling to a touch sensor. Such capacitive coupling may be achieved from a user, via a stylus, an active element such as an electronic pen (e-pen), and/or any other element implemented to perform capacitive coupling to the touch sensor. In some examples, note that the one or more touch sensors **1410** are also implemented to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from a user, such as a user's finger, to the one or more touch sensors **1410**).

[0162] At the top of the diagram, different respective users interact with one or more touch sensors **1410** using electronic pens (e-pens). The e-pens are implemented to transmit a signal that is detected by the one or more touch sensors **1410**. When different respective signals are transmitted from the different respective e-pens, the one or more touch sensors **1410** is implemented to detect which of the e-pens (and correspondingly which of the users) is interacting with the one or more touch sensors **1410**.

[0163] At the bottom of the diagram, one or more processing modules **1430** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **1430** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **1430**. A first group of one or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **1410**.

[0164] In addition, a first DSC **28** is implemented to drive and simultaneously to sense a first pen signal to an e-pen **#1**. The e-pen **#1** is associated with the user **#1**. A second DSC **28** is implemented to drive and simultaneously to sense a second pen signal to an e-pen **#2**. The e-pen **#2** is associated with the user **#2**. Note that any number of additional DSCs implemented to drive and simultaneously sense additional pens signals to additional e-pens may also be implemented.

[0165] In an example of operation and implementation, user **#1** uses the e-pen **#1** to interact with the one or more touch sensors **1410**. When doing so, the e-pen **#1** transmits the first pen signal that is capacitively coupled via capacitive coupling (CC) to the one or more touch sensors **1410**. The one or more processing modules **1430** is configured to detect the first pen signal via one or more of the DSCs **28** that are coupled between the one or more processing modules **1430** and the one or more touch sensors **1410**. The one or more processing modules **1430** is configured to discriminate the first pen signal from the respective signals that are driven from the one or more of the DSCs **28** that are coupled between the one or more processing modules **1430** and the one or more touch sensors **1410**. The one or more processing modules **1430** is configured to identify not only the interaction of an e-pen with the one or more touch sensors **1410**, but also configured to identify which e-pen (e.g., and which e-pen associated with which respective user) is interacting with the one or more touch sensors **1410**.

[0166] FIG. **15** is a schematic block diagram of an embodiment **1500** of a user identification capable touch sensor implemented with conductive mats associated with users in accordance with the present invention. Note that the conductive mats may be implemented in the floor in any of a variety of ways. The conductive mats may include one or more of an in-floor sensor, a transducer, an actuator, etc. A touch sensor system includes one or more touch sensors **1510**. The one or more touch sensors **1510** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types. The one or more touch sensors **1510** are implemented to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from

a user to the one or more touch sensors **1510**).

[0167] At the top of the diagram, different respective users are associated with different respective conductive mats. A conductive mat is implemented to couple a signal via a user that is detected by the one or more touch sensors **1510**. When different respective signals are transmitted from the different conductive mats, the one or more touch sensors **1510** is implemented to detect via which of the conductive mats this signal has been coupled (and correspondingly via which of the users this signal has been coupled). This allows the determination of which user is interacting with the one or more touch sensors **1510**.

[0168] At the bottom of the diagram, one or more processing modules **1530** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **1530** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **1530**. A first group of one or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **1510**.

[0169] In addition, a first DSC **28** is implemented to drive and simultaneously to sense a first user signal to conductive mat #1. The conductive mat #1 is associated with the user #1. A second DSC **28** is implemented to drive and simultaneously to sense a second user signal to conductive mat #2. The conductive mat #2 is associated with the user #2. Note that any number of additional DSCs implemented to drive and simultaneously sense additional user signals to additional conductive mats that may alternatively be associated with additional users may also be implemented.

[0170] In an example of operation and implementation, user #1 interacts with the one or more touch sensors **1510** when being associated with (e.g., standing on) conductive mat #1. When doing so, a first DSC **28** transmits a first user signal via conductive mat #1 that is capacitively coupled via capacitive coupling (CC) via the user #1 to the one or more touch sensors **1510**. The one or more processing modules **1530** is configured to detect the first user signal via one or more of the DSCs **28** that are coupled between the one or more processing modules **1530** and the one or more touch sensors **1510**. The one or more processing modules **1530** is configured to discriminate the first user signal from the respective signals that are driven from the one or more of the DSCs **28** that are coupled between the one or more processing modules **1530** and the one or more touch sensors **1510**. The one or more processing modules **1530** is configured to identify not only the interaction of a user with the one or more touch sensors **1510**, but also configured to identify which user (e.g., and which conductive mat associated with which respective user) is interacting with the one or more touch sensors **1510**.

[0171] FIG. **16** is a schematic block diagram of an embodiment **1600** of a user identification capable touch sensor implemented with seats associated with users in accordance with the present invention. A touch sensor system includes one or more touch sensors **1610**. The one or more touch sensors **1610** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types. The one or more touch sensors **1610** are implemented to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from a user to the one or more touch sensors **1610**).

[0172] At the top of the diagram, different respective users are associated with different respective seats. A seat is implemented to couple a signal via a user that is detected by the one or more touch sensors **1610**. When different respective signals are transmitted from the different seats, the one or more touch sensors **1610** is implemented to detect via which of the seats this signal has been coupled (and correspondingly via which of the users this signal has been coupled). This allows the determination of which user is interacting with the one or more touch sensors **1610**.

[0173] At the bottom of the diagram, one or more processing modules **1630** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **1630** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **1630**. A first group of one or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **1610**.

[0174] In addition, a first DSC **28** is implemented to drive and simultaneously to sense a first user signal to seat **#1**. The seat **#1** is associated with the user **#1**. A second DSC **28** is implemented to drive and simultaneously to sense a second user signal to seat **#2**. The seat **#2** is associated with the user **#2**. Note that any number of additional DSCs implemented to drive and simultaneously sense additional user signals to additional seats that may alternatively be associated with additional users may also be implemented.

[0175] In an example of operation and implementation, user **#1** interacts with the one or more touch sensors **1610** when being associated with (e.g., sitting in) seat **#1**. When doing so, a first DSC **28** transmits a first user signal via seat **#1** that is capacitively coupled via capacitive coupling (CC) via the user **#1** to the one or more touch sensors **1610**. The one or more processing modules **1630** is configured to detect the first user signal via one or more of the DSCs **28** that are coupled between the one or more processing modules **1630** and the one or more touch sensors **1610**. The one or more processing modules **1630** is configured to discriminate the first user signal from the respective signals that are driven from the one or more of the DSCs **28** that are coupled between the one or more processing modules **1630** and the one or more touch sensors **1610**. The one or more processing modules **1630** is configured to identify not only the interaction of a user with the one or more touch sensors **1610**, but also configured to identify which user (e.g., and which seat associated with which respective user) is interacting with the one or more touch sensors **1610**.

[0176] FIG. **17** is a schematic block diagram of an embodiment **1700** of a user identification capable touch sensor implemented with drive-sense circuit interfaces associated with users in accordance with the present invention. A touch sensor system includes one or more touch sensors **1710**. The one or more touch sensors **1710** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types. The one or more touch sensors **1710** are implemented to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from a user to the one or more touch sensors **1710**).

[0177] At the top of the diagram, different respective users are associated with different drive-sense circuit interfaces (DSC I/F). A DSC I/F is implemented to couple a signal via a user that is detected by the one or more touch sensors **1710**. Examples of such DSC I/F include any means by which a signal may be coupled via a user. Examples of a DSC I/F include one or more of a pen, a conductive mat, a seat, a seat belt, a cell phone, a smart phone, a key fob, a watch, an active wristband, a personal digital assistant (PDA), or a clip-on element. In some examples, note that the DSC I/F includes a DSC **28** therein (e.g., a DSC I/F includes a DSC **28** therein that is configured to transmit a signal via a user that is detected by the one or more touch sensors **1710**). In general, a DSC I/F may be viewed as any element, component, etc. that is configured to couple a signal via a user that is detected by the one or more touch sensors **1710**. In some examples, such coupling is via capacitive coupling (CC) from the DSC I/F to the user.

[0178] When different respective signals are transmitted from the different DSC I/Fs, the one or more touch sensors **1710** is implemented to detect via which of the DSC I/Fs this signal has been coupled (and correspondingly via which of the users this signal has been coupled). This allows the determination of which user is interacting with the one or more touch sensors **1710**.

[0179] At the bottom of the diagram, one or more processing modules **1730** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **1730** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **1730**. A first group of one or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **1710**.

[0180] In addition, a first DSC **28** is implemented to drive and simultaneously to sense a first user signal to DSC I/F #1. The DSC I/F #1 is associated with the user #1. A second DSC **28** is implemented to drive and simultaneously to sense a second user signal to DSC I/F #2. The DSC I/F #2 is associated with the user #2. Note that any number of additional DSCs implemented to drive and simultaneously sense additional user signals to additional DSC I/Fs that may alternatively be associated with additional users may also be implemented.

[0181] In an example of operation and implementation, user #1 interacts with the one or more touch sensors **1710** when being associated with DSC I/F #1. When doing so, a first DSC **28** transmits a first user signal via DSC I/F #1 that is capacitively coupled via capacitive coupling (CC) via the user #1 to the one or more touch sensors **1710**. The one or more processing modules **1730** is configured to detect the first user signal via one or more of the DSCs **28** that are coupled between the one or more processing modules **1730** and the one or more touch sensors **1710**. The one or more processing modules **1730** is configured to discriminate the first user signal from the respective signals that are driven from the one or more of the DSCs **28** that are coupled between the one or more processing modules **1730** and the one or more touch sensors **1710**. The one or more processing modules **1730** is configured to identify not only the interaction of a user with the one or more touch sensors **1710**, but also configured to identify which user (e.g., and which DSC I/F associated with which respective user) is interacting with the one or more touch sensors **1710**.

[0182] In an example of operation and implementation, a touch sensor system includes a plurality of touch sensors, a plurality of drive-sense circuits operably coupled to the plurality of touch sensors, memory that stores operational instructions, and a processing module operably coupled to the drive-sense circuit of the plurality of drive-sense circuits and to the memory.

[0183] When enabled, a drive-sense circuit of the plurality of drive-sense circuits is configured to drive a first signal via a single line coupling to a touch sensor of the plurality of touch sensors and simultaneously sense, via the single line, the first signal and, when present, a second signal coupled to the touch sensor of the plurality of touch sensors, wherein the second signal is uniquely associated with a user. The drive-sense circuit of the plurality of drive-sense circuits is also configured to process at least one of the first signal or the second signal to generate a digital signal that is representative of an electrical characteristic of the touch sensor of the plurality of touch sensors.

[0184] The processing module, when enabled, is configured to execute the operational instructions to process the digital signal to detect interaction of the user with the touch sensor. Also, the processing module, when enabled, is configured to execute the operational instructions to determine whether the interaction of the user with the touch sensor compares favorably with authorization. Based on unfavorable comparison of the interaction of the user with the touch sensor with the authorization, the processing module, when enabled, is configured to execute the operational instructions to abort execution of one or more operations associated with the interaction of the user with the touch sensor.

[0185] Alternatively, based on favorable comparison of the interaction of the user with the touch sensor with the authorization, the processing module, when enabled, is configured to execute the operational instructions to facilitate execution of the one or more operations associated with the interaction of the user with the touch sensor.

[0186] In some examples, the drive-sense circuit of the plurality of drive-sense circuits, when enabled, is further configured to drive the first signal via the single line coupling to the touch

sensor of the plurality of touch sensors and simultaneously sense, via the single line, the first signal and, when present, a third signal coupled to the touch sensor of the plurality of touch sensors, wherein the third signal is uniquely associated with another user and to process at least one of the first signal, the second signal, or the third signal to generate the digital signal that is representative of the electrical characteristic of the touch sensor of the plurality of touch sensors. The processing module, when enabled, is further configured to execute the operational instructions to process the digital signal to detect other interaction of the other user with the touch sensor, determine whether the other interaction of the other user with the touch sensor compares favorably with authorization. [0187] Based on unfavorable comparison of the other interaction of the other user with the touch sensor with the authorization, the processing module, when enabled, is configured to abort execution of one or more other operations associated with the other interaction of the other user with the touch sensor. Alternatively, based on favorable comparison of the other interaction of the other user with the touch sensor with the authorization, the processing module, when enabled, is configured to facilitate execution of the one or more other operations associated with the other interaction of the other user with the touch sensor.

[0188] In even other examples, another drive-sense circuit of the plurality of drive-sense circuits, when enabled, is configured to drive a third signal via another single line coupling to another touch sensor of the plurality of touch sensors and simultaneously sense, via the other single line, the third signal and, when present at a time that is different than when the second signal is present and sensed via the single line by the drive-sense circuit of the plurality of drive-sense circuits, the second signal coupled to the other touch sensor of the plurality of touch sensors and to process at least one of the third signal or the second signal to generate another digital signal that is representative of another electrical characteristic of the other touch sensor of the plurality of touch sensors.

[0189] The processing module, when enabled, is further configured to execute the operational instructions to process the other digital signal to detect other interaction of the user with the other touch sensor and to determine an angle of approach of the user to the touch sensor system based on the interaction of the user with the touch sensor and the other interaction of the user with the other touch sensor.

[0190] Note that the touch sensor system may be implemented using a variety of means include any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, and/or an array of buttons.

[0191] In addition, in some examples, the drive-sense circuit of the plurality of drive-sense circuits further includes a power source circuit operably coupled to the touch sensor of the plurality of touch sensors via the single line, wherein, when enabled, the power source circuit is configured to provide the first signal that includes an analog signal via the single line coupling to the touch sensor of the plurality of touch sensors, and wherein the analog signal includes at least one of a DC (direct current) component or an oscillating component. The drive-sense circuit of the plurality of drive-sense circuits further includes a power source change detection circuit operably coupled to the power source circuit.

[0192] When enabled, the power source change detection circuit is configured to detect an effect on the analog signal that is based on the electrical characteristic of the touch sensor of the plurality of touch sensors and to generate the digital signal that is representative of the electrical characteristic of the touch sensor of the plurality of touch sensors.

[0193] In some examples, the power source circuit includes a power source to source at least one of a voltage or a current to the touch sensor of the plurality of touch sensors via the single line. In some examples, the power source change detection circuit includes a power source reference circuit configured to provide at least one of a voltage reference or a current reference, and a comparator configured to compare the at least one of the voltage and the current provided to the touch sensor of the plurality of touch sensors to the at least one of the voltage reference and the current reference to

produce the analog signal.

[0194] In addition, in some examples, note that another drive-sense circuit of the plurality of drive-sense circuits, when enabled, configured to couple the second signal to the user via a drive-sense circuit interface that includes at least one of a pen, a conductive mat, a seat, a seat belt, a cell phone, a smart phone, a key fob, a watch, an active wrist-band, a personal digital assistant (PDA), or a clip-on element, and/or any other element via which a signal may be coupled via a user via capacitively coupling (CC) to one or more touch sensors.

[0195] FIG. **18** is a schematic block diagram of an embodiment **1800** of a user identification capable touch sensor implemented within an automobile in accordance with the present invention. A touch sensor system includes one or more touch sensors **1810**. The one or more touch sensors **1810** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types. The one or more touch sensors **1810** are implemented to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from a user to the one or more touch sensors **1810**).

[0196] At the top of the diagram, different respective users are associated with seats in the vehicle and/or different drive-sense circuit interfaces (DSC I/F). A seat and/or DSC I/F is implemented to couple a signal via a user that is detected by the one or more touch sensors **1810**. Examples of such DSC I/F include any means by which a signal may be coupled via a user. Examples of a DSC I/F include one or more of a pen, a conductive mat, a seat, a seat belt, a cell phone, a smart phone, a key fob, a watch, an active wrist-band, a personal digital assistant (PDA), or a clip-on element as described previously. In the context of the vehicle, any element within the vehicle that may be associated with a user may alternatively serve as a DSC I/F. For example, a seat within a vehicle may include various types of wiring, electronics, heating elements, cooling elements, actuators for seats positioning, a seatbelt, etc. Any such elements associated with the seat of the vehicle may serve as a DSC I/F. In an example of operation and implementation, a DSC is configured to transmit a signal via the DSC I/F, via a user, such that the signal is used to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from a user to the one or more touch sensors **1810**).

[0197] In some examples, note that the DSC I/F includes a DSC **28** therein (e.g., a DSC I/F includes a DSC **28** therein that is configured to transmit a signal via a user that is detected by the one or more touch sensors **1810**). In general, a DSC I/F may be viewed as any element, component, etc. that is configured to couple a signal via a user that is detected by the one or more touch sensors **1810**. In some examples, such coupling is via capacitive coupling (CC) from the DSC I/F to the user.

[0198] At the bottom of the diagram, one or more processing modules **1830** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **1830** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **1830**. A first group of one or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **1810**.

[0199] In addition, a first DSC **28** is implemented to drive and simultaneously to sense a first user signal to seat #**1** and/or DSC I/F #**1**. The seat #**1** and/or DSC I/F #**1** is associated with the user #**1**. A second DSC **28** is implemented to drive and simultaneously to sense a second user signal to seat #**2** and/or DSC I/F #**2**. The seat #**2** and/or DSC I/F #**2** is associated with the user #**2**. Note that any number of additional DSCs implemented to drive and simultaneously sense additional user signals to additional seats and/or DSC I/Fs that may alternatively be associated with additional users may

also be implemented.

[0200] In an example of operation and implementation, user #1 interacts with the one or more touch sensors **1810** when being associated with DSC I/F #1. When doing so, a first DSC **28** transmits a first user signal via DSC I/F #1 that is capacitively coupled via capacitive coupling (CC) via the user #1 to the one or more touch sensors **1810**. The one or more processing modules **1830** is configured to detect the first user signal via one or more of the DSCs **28** that are coupled between the one or more processing modules **1830** and the one or more touch sensors **1810**. The one or more processing modules **1830** is configured to discriminate the first user signal from the respective signals that are driven from the one or more of the DSCs **28** that are coupled between the one or more processing modules **1830** and the one or more touch sensors **1810**. The one or more processing modules **1830** is configured to identify not only the interaction of a user with the one or more touch sensors **1810**, but also configured to identify which user (e.g., and which DSC I/F associated with which respective user) is interacting with the one or more touch sensors **1810**.

[0201] FIG. **19** is a schematic block diagram of another embodiment **1900** of a user identification capable touch sensor implemented within an automobile in accordance with the present invention. A touch sensor system includes one or more touch sensors **1910**. The one or more touch sensors **1910** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types. The one or more touch sensors **1910** are implemented to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from a user to the one or more touch sensors **1910**).

[0202] At the top of the diagram, a user is associated with a seat in the vehicle and/or a drive-sense circuit interfaces (DSC I/F). A seat and/or DSC I/F is implemented to couple a signal via the user that is detected by the one or more touch sensors **1910**. Examples of such DSC I/F include any means by which a signal may be coupled via a user. Examples of a DSC I/F include one or more of a pen, a conductive mat, a seat, a seat belt, a cell phone, a smart phone, a key fob, a watch, an active wrist-band, a personal digital assistant (PDA), or a clip-on element as described previously. In the context of the vehicle, any element within the vehicle that may be associated with a user may alternatively serve as a DSC I/F. For example, a seat within a vehicle may include various types of wiring, electronics, heating elements, cooling elements, actuators for seats positioning, a seatbelt, passenger/driver detection functionality, etc. Any such elements associated with the seat of the vehicle may serve as a DSC I/F. In an example of operation and implementation, a DSC is configured to transmit a signal via the DSC I/F, via a user, such that the signal is used to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from a user to the one or more touch sensors **1910**).

[0203] In some examples, note that the DSC I/F includes a DSC **28** therein (e.g., a DSC I/F includes a DSC **28** therein that is configured to transmit a signal via a user that is detected by the one or more touch sensors **1910**). In general, a DSC I/F may be viewed as any element, component, etc. that is configured to couple a signal via a user that is detected by the one or more touch sensors **1910**. In some examples, such coupling is via capacitive coupling (CC) from the DSC I/F to the user.

[0204] At the bottom of the diagram, one or more processing modules **1930** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **1930** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **1930**. A first group of one or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **1910**.

[0205] In addition, a first DSC **28** is implemented to drive and simultaneously to sense a first user signal to seat and/or DSC I/F. The seat and/or DSC I/F is associated with the user **#1**. In this diagram, only a single DSC/first DSC **28** is configured to couple a signal via a user via seat and/or DSC I/F to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from the user to the one or more touch sensors **1910**).

[0206] In an example of operation and implementation, the user interacts with the one or more touch sensors **1910** when being associated with seat and/or DSC I/F. When doing so, a first DSC **28** transmits a first user signal via DSC I/F that is capacitively coupled via capacitive coupling (CC) via the user to the one or more touch sensors **1910**. The one or more processing modules **1930** is configured to detect the first user signal via one or more of the DSCs **28** that are coupled between the one or more processing modules **1930** and the one or more touch sensors **1910**. The one or more processing modules **1930** is configured to discriminate the first user signal from the respective signals that are driven from the one or more of the DSCs **28** that are coupled between the one or more processing modules **1930** and the one or more touch sensors **1910**. The one or more processing modules **1930** is configured to identify not only the interaction of a user with the one or more touch sensors **1910**, but also configured to identify the user (e.g., and which DSC I/F associated with which respective user) is interacting with the one or more touch sensors **1910**.

[0207] In automotive touch screen applications (e.g., such as with respect to FIG. **18** and/or FIG. **19**), some features of the one or more touch sensors are disabled when the vehicle is in motion. This is a safety measure deigned to prevent driver distraction. The unique identification of users as described herein, e.g., the driver of the vehicle, allows for the discrimination of the driver from the passenger so that the passenger can interact with the one or more touch sensors while the vehicle is in motion while the driver cannot interact with the one or more touch sensor. This allows for the passenger to continue to interact with the one or more touch sensors while the driver is not permitted to do so.

[0208] Note that there may be some situations in which only identification of the driver is desirable (e.g., such as in FIG. **19**). For example, there may be instances in which any user besides the driver of the vehicle is authorized to interact with the one or more touch sensors (e.g., while vehicle is in motion). However, such functionality may be included so that unique identification of each of the respective users within the vehicle is made (e.g., the driver, one or more passengers, etc.).

[0209] In an example of operation and implementation, a DSC **28** is configured to drive the signal that is transmitted via capacitive coupling (CC) to a user (e.g., the driver). Such capacitive coupling (CC) to the user may be implemented via any number of means including those described above. Note that the signal from the DSC **28** may operate at a unique frequency (or multiple frequencies independently or simultaneously). The frequency can hop on a pre-arranged pattern or a handshake may be established with a one or more processing modules **1930**, and the DSC is directed by the one or more processing modules **1930** which frequency to use.

[0210] In some examples, the signal transmitted from the DSC **28** that is coupled via the user includes an Identifier (ID) code that is also broadcast providing multi-factor disambiguation. In certain examples, the DSC **28** is powered by an electronics power supply already in the seat of the vehicle (e.g., passenger detect, heated seats, power controls, etc.) For power efficiency, the broadcasting driver can be turned on (or even cycled only when there is a driver/passenger detected in the corresponding seat). The capacitive coupling (CC) coupling can be done through conductive fibers in the seat, a conductive pad inside the seat or any other means by which capacitively coupling (CC) couple via the user may be performed.

[0211] Also, in some examples, capacitive sensors in the driver and passenger seats are employed in a feedback loop to the one or more processing modules **1930**. These sensors can be connected to the same one or more processing modules **1930** that is driving the on-board one or more touch sensors **1910**. Initially, for power management, the seat sensors could be in a low power (or disconnected) state. When a user interacts with the one or more touch sensors **1910**, the one or

more processing modules **1930** activates the sensors in the seats using a unique frequency for the driver and passenger. If the touch on the one or more touch sensors **1910** is registered using the driver-assigned frequency, the one or more processing modules **1930** will not respond with a touch activation. If the touch is registered using the passenger frequency, touch events are reported by the one or more processing modules **1930**. If both frequencies are registered, the touch one or more processing modules **1930** would not respond.

[0212] Note that there are many variations to such unique user identification techniques. In addition, as described in certain of the following diagrams, additional functionality may be included to identify one or more users uniquely alternatively to or in conjunction with the unique signaling being coupled via a user including detection of a user hovering over the one or more touch sensors, detection of the angle of approach by which a user is approaching the one or more touch sensors, etc.

[0213] FIG. **20** is a schematic block diagram of an embodiment **2000** of a user identification capable touch sensor in accordance with the present invention. A touch sensor system includes one or more touch sensors **2010**. The one or more touch sensors **2010** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types. The one or more touch sensors **2010** are implemented to detect user interaction based on user touch (e.g., via capacitive coupling (CC) from a user to the one or more touch sensors **2010**).

[0214] In addition, the one or more touch sensors **2010** is configured to detect the presence of the user before physically touching the one or more touch sensors **2010**. For example, as a user is initiating interaction with the one or more touch sensors **2010**, the one or more touch sensors **2010** is configured to detect the existence of the user proximity to the touchscreen. For example, considering a three-dimensional space, XYZ, where X and Y are the horizontal and vertical axes in the diagram and Z is the axis extending out of and into the diagram, as a user is approaching the one or more touch sensors **2010**, the one or more touch sensors **2010** is configured to detect the existence and location of the user in that process.

[0215] As described with respect to other diagrams, one or more processing modules is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules. A first group of one or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **2010**.

[0216] In some examples, the one or more processing modules determines or receives information corresponding to one or more known locations of one or more users with respect to the one or more touch sensors **2010** (e.g., which may be known beforehand, predetermined, determined based on detection of the one or more users, etc.). In such situations, the one or more processing modules is configured to use the information corresponding to the one or more known locations of the one or more users in accordance with determining the angle of approach of the one or more users to the one or more touch sensors **2010**.

[0217] Considering a user depicted on the left-hand side of the diagram, at different respective and successive times 1, 2, 3, as the user is approaching the one or more touch sensors **2010**, the one or more processing modules is configured to determine the position of the user with respect to the three-dimensional space, XYZ, in reference to the one or more touch sensors **2010**. For example, the one or more processing modules is configured to determine the position of the user at time 1 and subsequently a different position of the user at time 2. The one or more touch sensors modules then estimates the angle of approach of the user to the one or more touch sensors **2010** based on

these two positions.

[0218] In addition, the one or more processing modules is configured to perform comparison of a first angle of approach of first user interaction with a second angle of approach of second user interaction to determine which respective user is initiating interaction with the one or more touch sensors **2010**.

[0219] FIG. **21** is a schematic block diagram of another embodiment **2100** of a user identification capable touch sensor in accordance with the present invention. This diagram shows the one or more touch sensors **2010** is including a flat surface. Note that the angle of approach may be determined based on with respect to normal of the surface of one or more touch sensors **2010** for the actual surface of one or more touch sensors **2010** themselves. Alternatively, the angle of approach may be determined based on three-dimensional vector extending from the surface of the one or more touch sensors **2010**.

[0220] In an example, in the three-dimensional space, XYZ, consider that the position of the user time 1 is estimated to be (X1, Y1, Z1), and that the that the position of the user time 2 is estimated to be (X2, Y2, Z2), then the angle of approach of the user initiating interaction with the one or more touch sensors **2010** is based on a vector extending from the one or more touch sensors **2010** as defined by $([X2-X1], [Y2-Y1], [Z2-Z1])$.

[0221] In a specific example, in the three-dimensional space, XYZ, consider that the position of the user time 1 is estimated to be (1, 1, 5), and that the that the position of the user time 2 is estimated to be (5, 5, 1), then the angle of approach of the user initiating interaction with the one or more touch sensors **2010** is based on a vector extending from the one or more touch sensors **2010** as defined by $([X2-X1], [Y2-Y1], [Z2-Z1]) = ([1-5], [1-5], [5-1]) = (-4, -4, 4)$. In this specific example, the one or more processing modules is configured to determine that this angle of approach is associated with a user located approximately to the left-hand side or left-hand portion of the one or more touch sensors **2010**.

[0222] Alternatively, if the angle approach corresponded to a three-dimensional vector extending from the right-hand side or right hand portion of the one or more touch sensors **2010**, then the one or more processing modules that this angle of approach is associated with a user located approximately to the right-hand side or right-hand portion of the one or more touch sensors **2010**.

[0223] In an example of operation and implementation, consider that the one or more touch sensors **2010** are implemented within the vehicle that includes the driver's seat on the left-hand side of the one or more touch sensors **2010**. When the angle of approach of the user to the one or more touch sensors **2010** is determined to be from the left-hand side or left-hand portion of the one or more touch sensors **2010**, then the one or more processing modules determines that such user interaction is associated with the driver. Alternatively, when the angle of approach of the user to the one or more touch sensors **2010** is determined to be from the right-hand side or right-hand portion of the one or more touch sensors **2010**, then the one or more processing modules determines that such user interaction is associated with another passenger in the vehicle who is not the driver.

[0224] FIG. **22** is a schematic block diagram of an embodiment of a method **2200** for execution by one or more devices in accordance with the present invention. The method **2200** operates in step **2210** by transmitting a first signal via a first element associated with a first user. The first signal includes one or more characteristics that allow for unique identification of the first user. The method **2200** also operates in step **2220** by transmitting a second signal via a second element associated with a second user. The second signal includes one or more characteristics that allow for unique identification of the second user.

[0225] The method **2200** operates in step **2230** by detecting user interaction with one or more touch sensors. Note that the operations within the steps **2210**, **2220**, and **2230** may be performed using one or more DSCs that are configured to perform simultaneous transmit and receive via a single line (e.g., simultaneous drive and detect via a single line).

[0226] The method **2200** operates in step **2240** by determining whether user interaction with the

one or more touch sensors compares favorably with authorization. In some examples, the determination is made whether or not the user interaction is associated with second user and not the first user.

[0227] Based on a determination that the user interaction with the one or more touch sensors compares favorably with authorization, the method **2200** operates via step **2250** and step **2270** by permitting them processing the user interaction with the one or more touch sensors. In some examples, this involves execution of one or more operations associated with the user interaction with the one or more touch sensors. Such one or more operations may be associated with any one or more functions that are directed or controlled via the user interaction with the one or more touch sensors.

[0228] Alternatively, based on a determination that the user interaction with the one or more touch sensors compares unfavorably with authorization, the method **2200** operates via step **2250** and step **2260** blocking the user interaction with the one or more touch sensors. In some examples, this involves failing to execute or aborting execution of the one or more operations associated with the user interaction with the one or more touch sensors. In even other examples, this involves discarding the user interaction with the one or more touch sensors.

[0229] FIG. **23** is a schematic block diagram of another embodiment of a method **2300** for execution by one or more devices in accordance with the present invention. The method **2300** operates in step **2302** by operating one or more drive-sense circuits (DSCs) associated with one or more users and low-power mode. Such low-power mode may include one or more of reduced power, lower power, off, etc.

[0230] The method **2300** operates in step **2304** by monitoring for user interaction with one or more touch sensors. Based on failure to detect user interaction with the one or more touch sensors in step **2306**, the method **2300** loops back to step **2302**.

[0231] Based on detection of user interaction with the one or more touch sensors in step **2310**, the method **2300** operates in step **2310** by transmitting a first signal via a first element associated with a first user. The first signal includes one or more characteristics that allow for unique identification of the first user. The method **2300** also operates in step **2320** by transmitting a second signal via a second element associated with a second user. The second signal includes one or more characteristics that allow for unique identification of the second user.

[0232] Note that the operations within the steps **2302**, **2304**, **2306**, **2310**, and **2320** may be performed using one or more DSCs that are configured to perform simultaneous transmit and receive via a single line (e.g., simultaneous drive and detect via a single line).

[0233] The method **2300** operates in step **2340** by determining whether user interaction with the one or more touch sensors compares favorably with authorization. In some examples, the determination is made whether or not the user interaction is associated with second user and not the first user.

[0234] Based on a determination that the user interaction with the one or more touch sensors compares favorably with authorization, the method **2300** operates via step **2350** and step **2370** by permitting them processing the user interaction with the one or more touch sensors. In some examples, this involves execution of one or more operations associated with the user interaction with the one or more touch sensors. Such one or more operations may be associated with any one or more functions that are directed or controlled via the user interaction with the one or more touch sensors.

[0235] Alternatively, based on a determination that the user interaction with the one or more touch sensors compares unfavorably with authorization, the method **2300** operates via step **2350** and step **2360** blocking the user interaction with the one or more touch sensors. In some examples, this involves failing to execute or aborting execution of the one or more operations associated with the user interaction with the one or more touch sensors. In even other examples, this involves discarding the user interaction with the one or more touch sensors.

[0236] FIG. 24 is a schematic block diagram of an embodiment 2400 of a portion of a touch sensor that includes two touch sensors in accordance with the present invention. This diagram shows the first touch sensor that includes electrodes that are arranged in a first set of rows and a first of columns. In addition, the diagram shows a second set touch sensor that includes electrodes that are arranged in a second set of rows and a second set of columns. For example, the first touch sensor includes rows identified as row 1, sys. 1 (row 1, system 1), row 2, sys. 1 (row 2, system 1), and columns identified as col 1, sys. 1 (col 1, system 1), col 2, sys. 1 (col 2, system 1). The second touch sensor includes rows identified as row 1, sys. 2 (row 1, system 2), row 2, sys. 2 (row 2, system 2), and columns identified as col 1, sys. 2 (col 1, system 2), col 2, sys. 2 (col 2, system 2). [0237] In this diagram as well as other examples in embodiments included herein, note that while the configuration of the respective touch sensors (e.g., two touch sensors in this particular diagram) are shown in a row and column format, in general, the configuration of a touch sensor including respective electrodes that are implemented and two were more touch sensors may be arranged in any desired configuration in accordance with any desired pattern (e.g., Manhattan pattern, diamond pattern, and/or any other desired configuration in accordance with any desired pattern). In addition, note that land multiple respective touch sensors are implemented, any two were more of them may be implemented in different configurations in accordance with different patterns. For example, at first touch sensor may be implemented in accordance with a Manhattan pattern, while a second touch sensor may be implemented in accordance with a diamond pattern. In general, different respective touch sensors implemented within the system including two or more touch sensors may be independently implemented in accordance with any desired number of configurations in accordance with any desired number of desired patterns.

[0238] In addition, note that the two or more touch sensors 1410 may be of any of a variety of one or more types including rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types.

[0239] In an example of operation and implementation, the two respective touch sensors operate independently of one another, such that one of the touch sensors is redundant to the other. In another example of operation and implementation, the two respective time sensors operate cooperatively with respect one another such that their operation is cooperative and may transition in and out of different perspective modes of operation including those in which they both operate simultaneously, in which only one of them is operating at a time, in which one of them is operating to verify the operation of the other, in which there is operation in accordance with one or more power management considerations, and/or other modes of operation.

[0240] In some examples as described herein, a single Procap sensor is connected to two independent and redundant touch systems consisting of all electronics, power supply, connectors, etc. Although two systems provide redundancy, this can be extended to n systems, where n is a positive integer greater than or equal to 3. In this diagram particularly, with respect to one possible example, a single Procap sensor, showing a Manhattan pattern, is divided up into to two respective touch sensors. By taking every other row and column to be used, respectively as the first and second touch sensors. Each section is connected to an independent touch system. Each touch system can also communicate with each other if desired in some embodiments.

[0241] Many advantages are provided by constructing an overall touch system in this manner. For example, in one implementation, it uses the same technology for both sensor systems. This can provide for lower cost than combining two complete systems of dissimilar technologies. It can operate in hi-resolution mode with both touch systems operating. In addition, it is fully functional in a lower resolution mode if one of the touch systems fails (e.g., in a failure mode, the operation can be automatically adapted for optimal operation at reduced resolution). It can be operated in a

single touch sensor mode for power savings. Also, a single touch sensor provides a low profile of a true zero-height profile for in-cell systems (e.g., in accordance with a redundant touch in an in-cell implementation). The two touch systems can query each other to verify full functionality and report deviations from that expectation. Also, it can be constructed using a wide variety of single and multi-layer materials depending on cost, ergonomic, environmental or industrial design requirements. Also, in a failure situation with respect to one or more of the touch sensors, the working system can “call home” and a replacement unit can be sent to the customer without the customer even knowing that one system is down.

[0242] FIG. 25 is a schematic block diagram of an embodiment 2500 of a touch sensor that includes three touch sensors in accordance with the present invention. This diagram shows three respective touch sensors that each respectively include electrodes that are arranged in respective sets of rows and columns. For example, the first touch sensor includes rows identified as row 1, sys. 1 (row 1, system 1), row 2, sys. 1 (row 2, system 1), and columns identified as col 1, sys. 1 (col 1, system 1), col 2, sys. 1 (col 2, system 1). The second touch sensor includes rows identified as row 1, sys. 2 (row 1, system 2), row 2, sys. 2 (row 2, system 2), and columns identified as col 1, sys. 2 (col 1, system 2), col 2, sys. 2 (col 2, system 2). The third touch sensor includes rows identified as row 1, sys. 3 (row 1, system 3), row 2, sys. 3 (row 2, system 3), and columns identified as col 1, sys. 3 (col 1, system 3), col 2, sys. 3 (col 2, system 3).

[0243] In an example of operation and implementation, the three respective touch sensors operate independently of one another. For example, the first touch sensor operates primarily, and the two other touch sensors operate redundantly to the first touch sensor. In another example of operation and implementation, the three respective touch sensors operate cooperatively with respect one another such that their operation is cooperative and may transition in and out of different perspective modes of operation including those in which they both operate simultaneously, in which only one of them is operating at a time, in which one of them is operating to verify the operation of the other, in which there is operation in accordance with one or more power management considerations, and/or other modes of operation.

[0244] FIG. 26 is a schematic block diagram of an embodiment 2600 of a that includes n touch sensors in accordance with the present invention, where n is a positive integer greater than or equal to 3. This diagram shows n (where n is a positive integer greater than or equal to 3) respective touch sensors that each respectively include electrodes that are arranged in respective sets of rows and columns. For example, the first touch sensor includes rows identified as row 1, sys. 1 (row 1, system 1), row 2, sys. 1 (row 2, system 1), and columns identified as col 1, sys. 1 (col 1, system 1), col 2, sys. 1 (col 2, system 1). The second touch sensor includes rows identified as row 1, sys. 2 (row 1, system 2), row 2, sys. 2 (row 2, system 2), and columns identified as col 1, sys. 2 (col 1, system 2), col 2, sys. 2 (col 2, system 2). The nth touch sensor includes rows identified as row 1, sys. n (row 1, system n), row 2, sys. n (row 2, system n), and columns identified as col 1, sys. n (col 1, system n), col 2, sys. n (col 2, system n). In general, any desired number of touch sensors may be implemented within a given device.

[0245] FIG. 27 is a schematic block diagram of an embodiment 2700 of a touch sensor system in accordance with the present invention. In this diagram, on the lower right-hand side, a cross-section of two or more touch sensors is shown. In general, note that any desired number of touch sensors may be implemented. A number of DSCs are implemented to drive and simultaneously to sense signals via the respective electrodes of the respective touch sensors. For example, a first group of DSCs are implemented to drive and simultaneously to sense signals via the respective electrodes of the first touch sensor. A second group of DSCs are implemented to drive and simultaneously to sense signals via the respective electrodes of the second touch sensor.

[0246] In this diagram, different respective processing modules are implemented for the respective touch sensors. Also, with respect to the one or more processing modules included in this diagram and/or any other diagram herein, note that the one or more processing modules 1430 may include

integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules.

[0247] For example, for the first touch sensor, referenced as system **1**, one or more processing modules **2710** is coupled to the first group of DSCs that are implemented to drive and simultaneously to sense signals via the respective electrodes of the first touch sensor. Similarly, for the second touch sensor, referenced as system **2**, one or more processing modules **2720** is coupled to the second group of DSCs that are implemented to drive and simultaneously to sense signals via the respective electrodes of the second touch sensor. When more than two respective touch sensors are implemented, for the nth touch sensor, referenced as system n, one or more processing modules **2730** is coupled to the nth group of DSCs that are implemented to drive and simultaneously to sense signals via the respective electrodes of the nth touch sensor.

[0248] If desired in certain embodiments, one or more switching networks **2740** are implemented to allow selective coupling of the respective groups of DSCs to the respective electrodes of the respective touch sensors. In addition, with respect to a single touch sensor, note that different respective subsets of the electrodes therein may be operated at different respective times.

[0249] In an example of operation and implementation, considering the system **1**, the one or more processing modules **2710** is configured via the one or more switching networks **2740** to drive and simultaneously to sense signals via different respective subsets of the electrodes of the first touch sensor. For example, any particular example, only the every Xth row electrode and only the every Yth column electrode (where X and Y are respective positive integers greater than or equal to 2) are operational at a given time. Then, have a different time, only the every Ath row electrode and only the every Bth column electrode (where A and B are respective positive integers greater than or equal to 2) are operational. In general, different respective modes of operation that use different respective subsets of the electrodes of the first touch sensor at different times. Similar operation may be performed with respect to the second touch sensor and optionally any other touch sensors as well.

[0250] Also, the first touch sensor, the second touch sensor, and optionally any additional touch sensors, may be implemented to operate cooperatively such that communication is performed between the respective one or more processing modules associated there with. For example, the one or more processing modules **2710** associated with the first touch sensor and the one or more processing modules **2720** associated with the second touch sensor are in communication with one another via one or more communication paths. The respective one or more processing modules **2710** and **2720** operate and coordinate the operation of the first touch sensor and the second touch sensor. In general, when more than two touch sensors are implemented, the respective one or more processing modules associated with each of the respective touch sensors may operate cooperatively with one another to enter into and switch among various modes of operation.

[0251] In certain of the subsequent diagrams, different respective touch sensors are sometimes referred to as different respective systems. For example, a first system corresponds to the electrodes, one or more processing modules, one or more DSCs, etc. associated with a first touch sensor. A second system corresponds to the electrodes, one or more processing modules, one or more DSCs, etc. associated with a second touch sensor.

[0252] FIG. **28** is a schematic block diagram of another embodiment **2800** of a touch sensor system in accordance with the present invention. This diagram has some similarities to the previous diagram, with at least one difference being that one or more processing modules **2810** is implemented to coordinate operation of the respective touch sensors (e.g., associated with system **1**, **2**, and optionally up to n, where n is a positive integer greater than or equal to 3). Note that one or more switching networks **2840** may optionally be implemented to allow selectivity (e.g., in cooperation with and/or via direction or instruction from the one or more processing modules **2010**) regarding which respective touch sensors are operational at any given time, the operational mode by which any one or more of the touch sensors is operational at a given time, which

respective electrodes of any one or more of the touch sensors is operational at a given time, etc.

[0253] FIG. **29A** is a schematic block diagram of another embodiment of a method **2900** for execution by one or more devices in accordance with the present invention. The method **2900** operates by operating a first system in step **2910**. The method **2900** operates by operating a second system in step **2920**. Note that the second system may be operated redundantly to or alternatively to the first system. In certain embodiments, a method **2900** also operates by operating an nth system in step **2930**, where n is a positive integer greater than or equal to 3. Note that the nth system may be operated redundantly to or alternatively to the first and/or second systems.

[0254] In addition, note that the operations of the steps **2910** and **2920** may be operated independently with respect one another and/or simultaneously. In some examples, note that the operations of the steps **2910**, **2920**, and **2930** may be operated independently with respect one another and/or simultaneously.

[0255] FIG. **29B** is a schematic block diagram of another embodiment of a method **3000** for execution by one or more devices in accordance with the present invention. The method **2901** operates by operating a first system in step **2911**. The method **2901** operates by operating a second system in step **2921** cooperatively with the first system. In certain embodiments, a method **2901** also operates by operating an nth system in step **2931**, where n is a positive integer greater than or equal to 3, cooperatively with the first and second systems.

[0256] In this embodiment, when operating only the first system, the overall touch system operates based on a first resolution. When operating using both the first and second systems, the overall touch system operates based on a second resolution that is different than the first resolution. When operating using the first, second, and up to the nth systems, the overall touch system operates based on an nth resolution that is different than the first resolution and the second resolution. In addition, note that different respective granularity is within each respective first, second, etc. resolutions may be performed by operating different respective subsets of the electrodes associated with the different respective systems.

[0257] FIG. **30A** is a schematic block diagram of another embodiment of a method **3000** for execution by one or more devices in accordance with the present invention. The method **3000** operates in step **3010** by operating based on the first system. The method **3000** operates in step **3020** by performing diagnostics on a second system.

[0258] In one example, when no failure is detected in step **3030**, the method **3000** loops back to the step **3010**. When one or more failures are detected in step **3030**, the method **3000** operates by performing one or more corrective actions in step **3035**. For example, various corrective actions may include in one or more of modifying the operational mode of the overall touch system, providing an error message, communicating failure of at least one aspect of at least one of the systems, requesting a replacement unit to be provided from a manufacturer and/or service provider, notifying a user, notifying the service provider, etc. In general, any number of different respective corrective actions may be performed when one or more failures is detected based on performing diagnostics on the second system in step **3020**. When possible, one or more corrective actions includes an automated process that attempts to mitigate or eliminate the error. For example, one possible corrective action may be to perform a power cycle of the for which one or more failures has been detected.

[0259] In another example, when no failure is detected in step **3030**, the method **3000** operates by operating based on the second system in step **3040**. The method **3000** operates in step **3050** by performing diagnostics on the first system.

[0260] In one example, when no failure is detected in step **3060**, the method **3000** loops back to the step **3010** or **3040**. When one or more failures are detected in step **3060**, the method **3000** operates by performing one or more corrective actions in step **3065**. For example, various corrective actions may include in one or more of modifying the operational mode of the overall touch system, providing an error message, communicating failure of at least one aspect of at least one of the

systems, requesting a replacement unit to be provided from a manufacturer and/or service provider, notifying a user, notifying the service provider, etc. In general, any number of different respective corrective actions may be performed when one or more failures is detected based on performing diagnostics on the first system in step **3050**. When possible, one or more corrective actions includes an automated process that attempts to mitigate or eliminate the error. For example, one possible corrective action may be to perform a power cycle of the for which one or more failures has been detected.

[0261] In another example, when no failure is detected in step **3060**, the method **3000** operates in step **3070** by operating using a fail-free or still operable system (e.g., the first and/or second system).

[0262] FIG. **30B** is a schematic block diagram of another embodiment of a method **3001** for execution by one or more devices in accordance with the present invention. The method **3001** operates in step **3011** by operating a first system. The method **3001** operates in step **3021** by operating a second system. The operation of the second systems may be performed redundantly to or cooperatively with the first system. The method **3001** operates in step **3030** by performing diagnostics on the first and/or second system.

[0263] When no failure is detected based on the first system and/or the second system in step **3041**, the method **3001** loops back to performing the operations within one or more of the steps **3011**, **3021**, and/or **3031**. When one or more failures is detected based on the first system and/or the second system in step **3041**, the method **3001** operates by performing one or more corrective actions. Some examples of such corrective actions are described above. In certain examples, the method **3001** operates in step **3061** by operating using a fail-free or still operable system (e.g., the first and/or second system).

[0264] FIG. **31** is a schematic block diagram of another embodiment of a method **3100** for execution by one or more devices in accordance with the present invention. The method **3100** operates in step **3110** by operating first system. The method **3100** operates in step **3120** by operating a second system. The method **3100** operates in step **3120** by operating a second system. The operation of the second systems may be performed redundantly to or cooperatively with the first system. The method **3100** operates in step **3010** by monitoring for one or more conditions warranting a power saving operational mode. Examples of one or more conditions warranting a power saving operational mode may include reduced battery life or battery life below a particular threshold, disconnection from AC power, one or more of the systems consuming energy at a rate or level that exceeds a particular threshold, reduced performance of one or more of the systems, and/or any other consideration.

[0265] When no condition warranting a power savings operational mode are detected in step **3140**, the method **3100** loops back to perform the operations within one or more of the steps **3110**, **3120**, and **3130**.

[0266] Alternatively, when one or more conditions warranting a power savings operational mode are detected in step **3140**, the method **3100** operates in step **3150** by operating in a power saving operational mode. Examples of the power saving operational mode may include operating in accordance with a reduced power, operating using fewer than all of the systems available within the overall touch sensor, operating using fewer than all of the electrodes within a given system, operating using only the first system or the second system but not both, etc.

[0267] The method **3100** also operates in step **3160** by monitoring for one or more conditions permitting exit from the power saving operational mode. Examples of one or more conditions warranting an exit from the power saving operational mode may include increased battery life or battery life above a particular threshold, connection or detection of reconnection to AC power, one or more of the systems consuming energy at a rate or level that is below a particular threshold, acceptable performance of performance of one or more of the systems, and/or any other consideration.

[0268] When one or more conditions warranting an exit from the power savings operational mode are detected in step **3170**, the method **3100** loops back to perform the operations within one or more of the steps **3110**, **3120**, and **3130**. Alternatively, when no condition warranting a power savings operational mode are detected in step **3170**, the method **3100** operates via step **3170** by continuing operating in the power saving operational mode in step **3150**. Alternatively, when no condition warranting a power savings operational mode are detected in step **3170**, the method **3100** operates via step **3170** by ending.

[0269] And certain touch sensor applications, it may be desirable to have one or more redundant touch systems. For example, in certain application areas including aviation, automotive, industrial, medical, maritime, etc., one or more redundant systems provides continued operation of the overall system even in the event of failure of one or more of the systems. In certain applications, having one or more redundant systems can provide for failsafe for nearly failsafe operation.

[0270] In some examples redundant systems can be constructed by combining independent systems of different touch technologies. Various examples of touch sensor technologies include one or more of Analog Resistive, infrared (IR) and Camera Optical, Surface Acoustic Wave, Ultrasound, Projected Capacitive, etc. In some examples, each of the respective systems includes its own respective power supply. In other examples, two or more of the respective systems operate using a common power supply.

[0271] Within some applications, it may be prohibitively costly and undesirable to have independent respective power supplies for each of the respective systems for any number of reasons (e.g., ergonomic, industrial design, or electrical reasons). As described herein with respect to certain examples of embodiments, a single Procap (projected-capacitive) sensor, which may be implemented to include both single layer and multi-layer, can be operated by two or more independent touch controllers (e.g., based on one or more processing modules and different respective groups of DSCs, one or more switching networks, and/or other components as described herein).

[0272] In certain implementations, a more or most likely point of failure within the overall touch sensor system is not the one or more sensors themselves (e.g., a touchscreen, the electrodes of the respective touch sensors, etc.), which are typically very robust both mechanically and electrically, but a more or most likely point of failure within the overall touch sensor system is the surrounding electronics, connectors, power supply, etc. as described herein, having cost-effective redundant systems for the higher-probability failure points is both desirable and realistic. This is a very flexible system that contains many advantages, embodiments, configurations, etc.

[0273] FIG. **32** is a schematic block diagram of an embodiment **3200** of a vehicle implemented with user-interactive glass feature in accordance with the present invention. A touch sensor system includes one or more touch sensors **3210**. The one or more touch sensors **3210** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, a film that includes any desired implementation of components to facilitate touch sensor operation, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types.

[0274] At the bottom left of the diagram, one or more processing modules **3230** is coupled to one or more drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **3230** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **3230**. One or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **3210**.

[0275] In this diagram, the one or more touch sensors **3210** are included within one or more vehicle

windows. In general, the one or more touch sensors **3210** may be included in any glass feature within the vehicle. The one or more processing modules **3230** is also configured to facilitate execution of one or more operations associated with the vehicle. Some examples of such operations include operation of a window motor **3240**, operation of window tint controller **3242**, operation of windshield wipers **3244**, operation of side and/or rearview mirror controller **3244**, and/or any other functions **3249**. Note that the coupling between the one or more processing modules **3230** and the various respective operations associated with the vehicle may also be made using one or more DSCs **28**. For example, the interaction and operation between one or more processing modules **3230** and the various components implemented within the vehicle to execute such operations may be made via one or more DSCs **28**.

[0276] In an example of operation and implementation, a user within the vehicle, such as a vehicle passenger sitting in a vehicle seat, interacts with the one or more touch sensors **3210** implemented within a vehicle window. The motion and/or touch on the window is detected and interpreted by the one or more processing modules **3230** in accordance with facilitating the execution of the motion and/or touch on the window. Note also that different respective motions and/or touches may correspond to different respective operations. In general, different respective motions and/or touches may correspond to different respective commands provided from a user to direct operation of one or more components, systems, modules, etc. of the vehicle. Some examples of such motions and/or touches on the window are described in the table in the lower right-hand portion of the diagram. In general, any desired mapping of different respective motions and/or touches may be assigned to any desired commands for action to be performed by one or more components, systems, modules, etc. of the vehicle. The examples provided are not an exhaustive list, and in general, any operations associated with the vehicle may be assigned to any desired motions and/or touches. In general, a motion *x* may be assigned for a command for action to perform an action *x*; similarly, a touch location *a* may be assigned for a command for action to perform an action *z*; where *x* and *a* are assignable, reconfigurable, programmable, etc.

[0277] FIG. **33** is a schematic block diagram of an embodiment **3300** of a shower stall implemented with user-interactive glass feature in accordance with the present invention. A touch sensor system includes one or more touch sensors **3310**. Note that the one or more touch sensors **3310** may be implemented and integrated within the glass of the shower stall. Alternatively, the one or more touch sensors **3310** may be implemented within one or more films that is/are located on the inside and/or the outside of the shower stall. The one or more touch sensors **3310** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, a film that includes any desired implementation of components to facilitate touch sensor operation, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types.

[0278] In addition, note that the one or more touch sensors **3310** may be implemented within nontransparent or opaque portions of the shower stall. For example, the one or more touch sensors **3310** need not be implemented within clear or transparent glass. The one or more touch sensors **3310** may be implemented within tile, travertine, knobs, water controllers, etc. and/or any other surface and/or component accessible to user within the shower stall.

[0279] At the bottom left of the diagram, one or more processing modules **3330** is coupled to one or more drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **3330** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **3330**. One or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **3310**.

[0280] In this diagram, the one or more touch sensors **3310** are included within one or more features within a shower glass and/or door. In general, the one or more touch sensors **3310** may be included in any glass feature within a home, building, place of business, etc. The one or more processing modules **3330** is also configured to facilitate execution of one or more operations associated with the environment in which the one or more touch sensors **3310** are implemented. Some examples of such operations in the context of a shower may include operation of water flow control **3340**, water temperature control **3342**, light control **3344** such as turning the light on or off or adjusting its brightness/dimming the light, and/or any other function associated with the environment in which the one or more touch sensors **3310** are implemented. Note that the coupling between the one or more processing modules **3330** and the various respective operations associated with the environment also may be made using one or more DSCs **28**. For example, the interaction and operation between one or more processing modules **3330** and the various components associated with the environment to execute such operations may be made via one or more DSCs **28**.

[0281] In an example of operation and implementation, a user within the shower interacts with the one or more touch sensors **3210** implemented within the environment of the shower stall. The motion and/or touch on the one or more touch sensors **3210** is detected and interpreted by the one or more processing modules **3230** in accordance with facilitating the execution of the motion and/or touch on the one or more touch sensors **3210**. Note also that different respective motions and/or touches may correspond to different respective operations. In general, different respective motions and/or touches may correspond to different respective commands provided from a user to direct operation of one or more components, systems, modules, etc. of the environment of the shower stall. Some examples of such motions and/or touches on the window are described in the table in the lower right-hand portion of the diagram. In general, any desired mapping of different respective motions and/or touches may be assigned to any desired commands for action to be performed by one or more components, systems, modules, etc. of the environment of the shower stall. The examples provided are not an exhaustive list, and in general, any operations associated with the environment of the shower stall may be assigned to any desired motions and/or touches. In general, a motion *x* may be assigned for a command for action to perform an action *x*; similarly, a touch location *a* may be assigned for a command for action to perform an action *z*; where *x* and *a* are assignable, reconfigurable, programmable, etc.

[0282] FIG. **34** is a schematic block diagram of an embodiment **3400** of a user-interactive glass feature implemented with one or more identifiers in accordance with the present invention. A touch sensor system includes one or more touch sensors **3410**. Note that the one or more touch sensors **3410** may be implemented and integrated within any type of element including glass, mirror, etc. Note that the one or more touch sensors **3410** may be implemented within one or more films that is/are located on the inside and/or the outside of such an element including glass, mirror, etc. The one or more touch sensors **3410** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, a film that includes any desired implementation of components to facilitate touch sensor operation, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types.

[0283] In addition, note that the one or more touch sensors **3410** may be implemented within nontransparent or opaque portions of the element including glass, mirror, etc. For example, the one or more touch sensors **3410** need not be implemented within clear or transparent glass.

[0284] At the bottom left of the diagram, one or more processing modules **3430** is coupled to one or more drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **3430** may include integrated memory and/or be coupled to other memory. At least some of the memory stores

operational instructions to be executed by the one or more processing modules **3430**. One or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **3410**.

[0285] In an example of operation and implementation, the one or more touch sensors **3410** are associated with an element on which one or more identifiers are implemented. Again, the one or more touch sensors **3410** may be implemented within the element in any of a number of ways included integrated therein, included in the film placed thereon, etc. For example, the element may include glass, mirror, a touchscreen, etc. The one or more identifiers may include printing, labeling, text, symbols, and/or any other indicators. The identifiers provide indication to a user interacting with the one or more touch sensors **3410** of where to interact in order to facilitate execution of one or more operations. For example, control for one or more elements associated with one or more identifiers is shown with respect to 4 different portions of the one or more touch sensors **3410** on the middle and right hand side portion of the diagram.

[0286] In general, if any desired number of regions associated with different respective identifiers may be included within the element that is associated with the one or more touch sensors **3410**. In addition, any desired number of sub-identifiers may be included with any one of the regions in which the element is partitioned. For example, considering a section **3** that includes the one or more identifiers **3**, there may be any number of sub-sections included therein. In general, any desired level of granularity, sub-division, etc. of the one or more identifiers, the one or more sub-identifiers, may be implemented with respect to the element that is associated with the one or more touch sensors **3410**.

[0287] Based upon user interaction with the one or more touch sensors **3410** and specifically on the one or more identifiers associated with the one or more touch sensors **3410**, the one or more processing modules **3430** facilitate execution of control of different respective operations. For example, interaction with the one or more identifiers **1** in the upper left-hand portion of the element on which the one or more identifiers are implemented facilitates execution of control of operations associated therewith.

[0288] In an example of operation and implementation, consider that the one or more identifiers **3** are associated with an audio system (e.g., such as may be implemented within a home, a place of business, a place of learning, etc.), The one or more sub-identifiers **3,1** through **3,4**, etc. are associated with particular operations of the audio system that may include any one or more of turning the system on or off, adjusting volume, controlling which speakers are operational, controlling the equalizer operation of the audio system, and/or any other operations associated with the audio system.

[0289] In some examples, the use of identifiers and/or sub-identifiers may facilitate better user interaction with the one or more touch sensors **3410**. Also, in other examples the use of identifiers allows for specific mapping of one or more portions of the one or more elements associated with the one or more touch sensors **3410** to be specifically assigned and mapped for different operations.

[0290] Note that the coupling between the one or more processing modules **3430** and the various respective functions associated with the identifiers also may be made using one or more DSCs **28**. For example, the interaction and operation between one or more processing modules **3430** and the various components associated with the identifiers to execute such functions may be made via one or more DSCs **28**.

[0291] The environments of application of such identifiers and/or sub-identifiers in conjunction with one or more touch sensors **3410** are myriad. Considering just some examples within a home, various user interactive operations may be implemented using one or more touch sensors **3410** that are associated with one or more elements and associated identifiers and/or sub-identifiers may include any one or more of thermostat controls, doorbells, light switches and/or controls, HVAC controls, security panels, door locking and/or unlocking, driveway gate control, etc. Such examples are not exhaustive, and in general, any desired user interaction with a control element may be

implemented in such a manner.

[0292] In general, any user interaction with a control element in any component and/or surface may be implemented using such identifiers and/or sub-identifiers in conjunction with one or more touch sensors **3410** in conjunction with one or more elements.

[0293] FIG. **35** is a schematic block diagram of an embodiment **3500** of a steering wheel implemented with a touch sensor in accordance with the present invention. A touch sensor system includes one or more touch sensors **3510**. In this diagram, the one or more touch sensors **3510** are implemented within the steering wheel that is implemented within a vehicle. Note that the one or more touch sensors **3510** may be implemented within one or more films that is/are located on the inside and/or the outside of the steering wheel. The one or more touch sensors **3510** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, a film that includes any desired implementation of components to facilitate touch sensor operation, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types. In addition, note that the one or more touch sensors **3510** may be implemented within nontransparent or opaque portions of the steering wheel.

[0294] At the bottom left of the diagram, one or more processing modules **3530** is coupled to one or more drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **3530** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **3530**. One or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **3510**.

[0295] Based upon user interaction with the one or more touch sensors **3510** associated with the steering wheel, the one or more processing modules **3530** facilitate execution of control of different respective functions associated with the vehicle. Any number of different functions **1** through **n** associated with the vehicle may be associated with user interaction with the one or more touch sensors **3510**.

[0296] Note that the coupling between the one or more processing modules **3530** and the various respective functions associated with the vehicle also may be made using one or more DSCs **28**. For example, the interaction and operation between one or more processing modules **3530** and the various components associated with the vehicle to execute such functions may be made via one or more DSCs **28**.

[0297] In some examples, a heads-up display (HUD) **3550** is also implemented in the vehicle. In some embodiments, a user interacts with the one or more touch sensors **3510** that are associated with the steering wheel to interact with the HUD **3550**. The HUD **3550** provides a visual representation of various respective operations associated with the vehicle. For example, any display related information that may be provided via a display implemented within the vehicle, such as may be implemented in the dashboard of the vehicle between the driver and front passenger seats, may alternatively or also be displayed via the HUD **3550**. Navigating and interacting throughout various menus associated with various functions, systems, etc. of the vehicle may be facilitated via the user interacting with the one or more touch sensors **3510** that are associated with the steering wheel in conjunction with the HUD **3550**.

[0298] In an example of operation and implementation, a driver of the vehicle performs a particular motion and/or touches a particular location on the steering wheel to bring up a main menu that is visible to the driver of the vehicle via the HUD **3550**. Then, based on the main menu displayed, the driver of the vehicle performs a particular motion and/or touches a particular location on the steering wheel to access a particular icon or portion of the main menu that is displayed via the HUD **3550**, and performs a particular motion and/or touches a particular location on the steering

wheel to select that particular icon or portion of the main menu that is displayed via the HUD **3550**. In general, user interactivity with the one or more functions, systems, etc. of the vehicle may be facilitated via the user interacting with the one or more touch sensors **3510** that are associated with the steering wheel in conjunction with the HUD **3550**.

[0299] FIG. **36** is a schematic block diagram of another embodiment **3600** of a steering wheel implemented with a touch sensor in accordance with the present invention. A touch sensor system includes one or more touch sensors **3610**. In this diagram, the one or more touch sensors **3610** are implemented within the steering wheel that is implemented within a vehicle. Note that the one or more touch sensors **3610** may be implemented within one or more films that is/are located on the inside and/or the outside of the steering wheel. The one or more touch sensors **3610** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, a film that includes any desired implementation of components to facilitate touch sensor operation, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types. In addition, note that the one or more touch sensors **3610** may be implemented within nontransparent or opaque portions of the steering wheel.

[0300] At the bottom left of the diagram, one or more processing modules **3630** is coupled to one or more drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **3630** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **3630**. One or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **3610**.

[0301] Based upon user interaction with the one or more touch sensors **3610** associated with the steering wheel, the one or more processing modules **3630** facilitate execution of control of different respective functions associated with the vehicle. Any number of different functions 1 through n associated with the vehicle may be associated with user interaction with the one or more touch sensors **3610**. In this diagram, the one or more processing modules **3630** facilitate execution of one or more operations associated with a heads up display (HUD) **3650**, and audio system **3652** (e.g., which may include one or more speakers, a voice recognition system, and/or any other audio related operations), and/or any other user interface **3659** that allows information to be provided to the driver of the vehicle and/or allows input from the driver of the vehicle to be received.

[0302] Note that the coupling between the one or more processing modules **3630** and the various respective functions associated with the vehicle also may be made using one or more DSCs **28**. For example, the interaction and operation between one or more processing modules **3630** and the various components associated with the vehicle to execute such functions may be made via one or more DSCs **28**.

[0303] In some examples, user interactivity with the steering wheel and the one or more touch sensors **3610** associated therewith is driven in a manner similar to selectivity that is performed using the tab button on the keyboard and the enter button on the keyboard. For example, on a keyboard, when navigating a menu with multiple icons, navigation through the respective icons currently displayed may be performed using the tab button on the keyboard and when the desired icon is highlighted or currently selected, pressing the enter button on the keyboard executes the operation associated with that icon that is highlighted or currently selected. Within the operation of the one or more touch sensors **3610** and the HUD **3650**, a particular motion and/or touches a particular location on the steering wheel (e.g., a tapping with the left index finger) performs the operation of navigation through the respective icons currently displayed via the HUD **3650**, and a particular motion and/or touches a particular location on the steering wheel (e.g., a tapping the steering wheel with the right index finger) executes the operation associated with that icon that is

highlighted or currently selected.

[0304] Note also that any desired mapping of user interaction with the one or more touch sensors **3610** associated with steering wheel may be made. For example, certain hand position on the steering wheel may be associated with a first operation, a particular pressure from the driver of the vehicle's hands on one or more portions of the steering wheel may be associated with a second operation, a particular movement of the driver of the vehicle's hands on one or more portions of the steering wheel may be associated with a third operation, a particular sequence of position, pressure, and/or movement of the driver of the vehicle's hands on one or more portions of the steering wheel may be associated with a fourth operation, etc. In general, any combination of various touches, positions, pressures, movements, sequences, tappings, rhythms, etc. and/or any other manner by which the driver of the vehicle may interact with the one or more touch sensors **3610** that are associated with steering wheel may be mapped and associated with various operations associated with the vehicle.

[0305] Note that interaction of the driver of the vehicle with the one or more touch sensors **3610** may be performed without the driver of the vehicle ever removing his or her hands from the steering wheel. The one or more processing modules **3630** facilitate interaction with the driver of the vehicle via one or more of the HUD **3650**, the audio system **3652**, and and/or another user interface **3659** based on one or more menus, one or more system information, and/or any other information.

[0306] FIG. **37** is a schematic block diagram of an embodiment **3700** of a field of view user-interactive glass feature in accordance with the present invention. In this diagram one or more touch sensors are associated with a window. The one or more touch sensors may be implemented in any of a variety of ways including integrated into the window, included in the film on any layer of the window, using one or more integrated touch sensors, using one or more electrodes, etc.

[0307] Different respective portions of the window and the associated portions of the one or more touch sensors that are associated with the window correspond to control operations associated with elements visible via the field of view of the window. For example, consider that the field of view of the window includes a building, and outdoor light, vehicle, a gate, the sprinkler system component, inground walkway lighting, etc. The respective portions of the one or more touch sensors that are associated with the window provide the control based on the associated with the portions of the window that include the respective elements via the field of view of the window.

[0308] For example, consider that the building is visible via the field of view of the window in a left-hand portion of the window and the inground walkway lighting is visible in the edit field of view of the window centrally below that left-hand portion of the window. Those portions of the one or more touch sensors that are located in the left-hand portion of the window provide touch control for the building (e.g., for any one or more of the respective components therein).

[0309] In an example of operation and implementation, the user interacts with the one or more touch sensors implemented in a left-hand portion of the field of view of the window to facilitate control of one or more aspects of the building and/or the inground walkway lighting. For example, a user interacting with the one or more touch sensors of the window that are included in the field of view of the window that includes the inground walkway lighting controls of the inground walkway lighting (e.g., turning them on, turning them off, controlling their brightness, etc. and/or any other control operation related to the gate inground walkway lighting).

[0310] In another example of operation and implementation, a user interacts with the one or more touch sensors implemented in an upper right-hand portion of the field of view of the window to facilitate control of the gate. For example, a user interacting with the one or more touch sensors of the window that are included in the field of view of the window that includes the gate controls of the gate (e.g., opening the gate, closing the gate, locking the gate, enabling the gate, disabling the gate, etc. and/or any other control operation related to the gate).

[0311] Similarly, with respect to the other portions of the field of view of the window, a user

interacting with the one or more touch sensors implemented in the respective portions of the field of view of the window allow the user to interact with those other components.

[0312] FIG. **38** is a schematic block diagram of another embodiment **3800** of a field of view user-interactive glass feature in accordance with the present invention. A touch sensor system includes one or more touch sensors **3810**. Note that the one or more touch sensors **3810** may be implemented and integrated within any type of element including glass, mirror, etc. Note that the one or more touch sensors **3810** may be implemented within one or more films that is/are located on the inside and/or the outside of such an element including glass, mirror, etc. The one or more touch sensors **3810** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, a film that includes any desired implementation of components to facilitate touch sensor operation, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types.

[0313] At the bottom left of the diagram, one or more processing modules **3830** is coupled to one or more drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **3830** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **3830**. One or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **3810**.

[0314] In an example of operation and implementation, the one or more touch sensors **3810** are associated with elements that are visible via different respective section and/or sub-section views of the field of view of the window. For example, control for one or more elements that are visible via 4 different respective section of the field of view of the window are associated with 4 different portions of the one or more touch sensors **3810** on the middle and right hand side portion of the diagram.

[0315] In general, if any desired number of regions associated with different respective section views and/or sub-section views of the field of view of the window that may be associated with the one or more touch sensors **3810**. In addition, any desired number of section views and sub-section views may be included with the field of view of the window. For example, considering a section **3** view that includes one or more elements therein based on the field of view of the window. Note that there may be any number of sub-sections included therein. In one specific example, the section **3** view includes one or more sub-section **3,1** through **3,4** views, etc. In general, any desired level of granularity, sub-division, etc. of the one or more section views, the one or more section views, may be implemented with respect to the field of view of the window that is associated with the one or more touch sensors **3810**.

[0316] Based upon user interaction with the one or more touch sensors **3810** and specifically on the one or more section views and/or sub-section views that are associated with the one or more touch sensors **3810**, the one or more processing modules **3830** facilitate execution of control of different respective operations. For example, interaction with the one or more section **1** view in the upper left-hand portion of the element on which the one or more identifiers are implemented execution of control of operations associated with one or more elements included within the section **1** view in the upper left-hand portion of the field of view of the window.

[0317] Note that the coupling between the one or more processing modules **3830** and the various respective functions associated with the one or more section views and/or sub-section views also may be made using one or more DSCs **28**. For example, the interaction and operation between one or more processing modules **3830** and the various components associated with the one or more section views and/or sub-section views to execute such functions may be made via one or more DSCs **28**.

[0318] FIG. 39 is a schematic block diagram of another embodiment 3900 of a field of view user-interactive glass feature in accordance with the present invention. In addition, in certain embodiments, identification of the location of a user and/or identification of the user who is interacting with the one or more touch sensors that are associated with the field of view of the window is used to perform dynamic modification of the sections and/or sub-sections within the field of view of the window. For example, one or more in floor sensors, transducers, actuators, etc. may be implemented to detect a user proximate to the window, interacting with the one or more touch sensors of the window, and/or who is likely to interact with the one or more touch sensors of the window. Based upon detection of the user, the respective one or more sections and/or sub-sections within the field of view of the window are dynamically modified based upon the expected field of view through the window based upon the location of the user.

[0319] In some examples, a signal is driven via capacitively coupling (CC) through the user to provide for unique identification of the user when interacting with the one or more touch sensors associated with the window. For example, when two respective users are interacting with the one or more touch sensors associated with the window, the two respective users may have different perspectives of the respective elements within the field of view of the window. The respective sections and/or sub-sections within the field of view of the window are dynamically adjusted appropriately for each of the two respective users when interacting with the one or more touch sensors associated with the window. For example, for a user on the left-hand side of the window, the sections and/or sub-sections within the field of view of the window are dynamically adjusted with reference to the one or more touch sensors associated with the window so that control and interactivity of the elements within the field of view from that user's perspective are appropriately aligned. Similarly, for user on the right-hand side of the window, the sections and/or sub-sections within the field of view of the window are dynamically adjusted with reference to the one or more touch sensors associated with the window so that control and interactivity of the elements within the field of view from that user's perspective are appropriately aligned. In this way, a particular portion of the one or more touch sensors can potentially provide control for different respective elements within the field of view of the window depending upon which user is interacting with the one or more touch sensors.

[0320] In an example of operation and implementation, with a reference back to FIG. 37, consider an example that a first user is located on the left-hand side of the window, and a second user is located on the right-hand side of the window. The first user views the building via a left-hand central portion of the window. The second user views that same building via a middle to right-hand portion of the window. One or more processing modules is implemented to detect not only be user interaction of the first user and the second user but also to discriminate which user interaction corresponds to the first user for the second user. As such, different respective portions of the one or more touch sensors associated with the window provide control for the same element within the field of view of the window, e.g., the building, based upon which user is interacting with the one or more touch sensors associated with the window based upon where that element within the field of view of the window, e.g., the building, is seen from the perspective of the two different users.

[0321] FIG. 40 is a schematic block diagram of another embodiment 4000 of a field of view user-interactive glass feature in accordance with the present invention. This diagram shows different respective windows, which have different respective one or more touch sensors associated therewith, within a building providing different respective fields of view. Note that some of the fields of view may have some overlap.

[0322] The different respective one or more touch sensors associated with the different respective windows of the building provide for user interaction with respect to those elements that are visible within the respective fields of view provided from the windows.

[0323] When there is overlap between two fields of view from two different windows, note that user interaction with the one or more touch sensors associated with those two different windows

may provide for control of the same element visible from those two fields of view from those two different windows.

[0324] Considering a specific example, consider that a sprinkler system is visible via the field of view **4** from window **4** and also via the field of view **5** from window **5**. User interaction with the appropriate portion of the one or more touch sensors that are associated with window **4** and also user interaction with the appropriate portion of the one or more touch sensors that are associated with window **5** will control the sprinkler system (e.g., turning it on, turning it off, controlling water only and flow, controlling the rate of operation of the components therein, any timing controls, etc. and/or any other control operations associated with this breaker system).

[0325] FIG. **41** is a schematic block diagram of an embodiment of another embodiment of a method **4100** for execution by one or more devices in accordance with the present invention. The method **4100** operates in step **4110** by detecting motion or touch on one or more touch sensors. As described herein, note that the one or more touch sensors may be implemented in any of a number of varieties including those described herein.

[0326] The method **4100** operates in step **4120** by processing the motion or touch. Based on a failure to perform identification of the motion or touch, the method **4100** operates via step **4130** and step **4135** by performing one or more operations associated with failure to identify the motion or touch. Some examples of such operations associated with failure to identify the motion or touch may include one or more of taking no action, notifying a user, reporting an error, etc., and/or any other appropriate operation.

[0327] Based upon identification of the motion or touch, the method **4100** operates by appropriately identifying the motion or touch in accordance with one or more categories of motion or touch.

[0328] Based upon identification of the motion or touch being associated with a first category of motion or touch, the method **4100** operates via step **4140** and step **4145** by facilitating execution of a first one or more actions.

[0329] Based upon failure to perform identification of the motion or touch being associated with a first category of motion or touch, the method **4100** operates via step **4140** to step **4150** by appropriately identifying the motion or touch in accordance with other of the one or more categories of motion or touch.

[0330] Based upon identification of the motion or touch being associated with a second category of motion or touch, the method **4100** operates via step **4150** and step **4155** by facilitating execution of a second one or more actions.

[0331] In general, this process of performing identification of the motion or touch being associated with different respective categories of motion or touch can be performed based on n number of categories of motion or touch.

[0332] For example, based upon failure to perform identification of the motion or touch being associated with first through n-1 categories of motion or touch, the method **4100** operates via step **4160** by appropriately identifying the motion or touch in accordance with the nth category of motion or touch.

[0333] Based upon identification of the motion or touch being associated with an nth category of motion or touch, the method **4100** operates via step **4160** and step **4165** by facilitating execution of an nth one or more actions. In the event that the identified motion or touch is not properly associated with any of the respective categories of motion or touch, the method **4100** ends, provides an error message, provides notification to the user, provide notification to one or more other devices, etc.

[0334] FIG. **42** is a schematic block diagram of an embodiment **4200** of a touchscreen implemented with an external controller in accordance with the present invention. In this diagram, one or more touch sensors **4210** and an external controller that includes one or more buttons are both controlled by one or more processing modules **4230**. Note that the one or more touch sensors **4210** may be of any variety and type as described herein. In some examples, the one or more touch

sensors **4210** are included within pad device, laptop, cell phone, smartphone, whiteboard, and interactive display, and navigation system display, and in vehicle display, etc., and/or any other type of device in which the one or more touch sensors **4210** may be implemented. Note that the manner, type, and variety of the respective one or more touch sensors may be of any desired type.

[0335] A touch sensor system includes one or more touch sensors **4210**. The one or more touch sensors **4210** may be of any of a variety of one or more types including any one or more of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, an array of buttons, a film that includes any desired implementation of components to facilitate touch sensor operation, and/or any other configuration by which interaction with the touch sensor may be performed. With respect to the various embodiments, implementations, etc. of various respective touch sensors as described herein, note that they may also be of any such variety of one or more types.

[0336] At the bottom of the diagram, one or more processing modules **4230** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **4230** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **4230**. A first group of one or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **4210**. A first group of one or more DSCs **28** is/are implemented to drive and simultaneously to sense respective one or more signals provided to the external controller (e.g., to the one or more respective buttons implemented therein). In some examples, a respective DSC is implemented to drive and simultaneously to sense a respective one or more signals provided to a respective button on the external controller. For example, a first DSC is implemented to drive and simultaneously to sense a first respective one or more signals provided to a first respective button on the external controller, and a second DSC is implemented to drive and simultaneously to sense a second respective one or more signals provided to a second respective button on the external controller.

[0337] Note that the very same one or more processing modules **4230** is configured to drive and simultaneously to sense respective one or more signals provided to both the one or more touch sensors **4210** and the external controller via the respective DSCs.

[0338] Note that control of the touchscreen may be effectuated based on user interaction with one or more of the buttons. Such one or more buttons associated with the external controller may be alternative to, in addition to, and/or cooperative in the control effectuated via the one or more touch sensors **4210**.

[0339] FIG. **43** is a schematic block diagram of various embodiment **4300** of touchscreens implemented with external controllers in accordance with the present invention. This diagram shows multiple different examples by which an external controller may be implemented in conjunction with one or more touch sensors **4310**.

[0340] Embodiment **4312** includes one or more touch sensors **4310** accompanied with an external controller that is implemented on a side of a touchscreen (e.g., on the left or right hand side of the touchscreen). Note that the very same one or more processing modules is configured to drive and simultaneously to sense respective one or more signals provided to both the one or more touch sensors **4310** and the external controller via the respective DSCs.

[0341] Embodiment **4320** includes one or more touch sensors **4310** accompanied with two external controllers that are implemented on the sides of a touchscreen. Note that the very same one or more processing modules is configured to drive and simultaneously to sense respective one or more signals provided to both the one or more touch sensors **4310** and also to both of the external controllers via the respective DSCs.

[0342] Embodiment **4330** includes one or more touch sensors **4310** accompanied with an external controller that is implemented on a top of a touchscreen. Note that the very same one or more processing modules is configured to drive and simultaneously to sense respective one or more

signals provided to both the one or more touch sensors **4310** and the external controller via the respective DSCs.

[0343] Embodiment **4340** includes one or more touch sensors **4310** accompanied with one or more external controllers that is/are implemented on a back of a touchscreen. Note that the very same one or more processing modules is configured to drive and simultaneously to sense respective one or more signals provided to both the one or more touch sensors **4310** and the one or more external controllers via the respective DSCs.

[0344] Embodiment **4350** includes one or more touch sensors **4310** accompanied with one or more external controllers that is/are tethered to the one or more touch sensors **4310**. Note that the very same one or more processing modules is configured to drive and simultaneously to sense respective one or more signals provided to both the one or more touch sensors **4310** and the one or more external controllers that is/are tethered via the respective DSCs. Note that the DSCs that are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more external controllers that is/are tethered may be implemented within the one or more external controllers that is/are tethered and/or the element that includes the one or more touch sensors **4310**.

[0345] Embodiment **4360** includes one or more touch sensors **4310** accompanied with one or more external controllers that is/are in wireless communication with the one or more touch sensors **4310**. Note that the one or more processing modules is configured to drive and simultaneously to sense respective one or more signals provided to the one or more touch sensors **4310**. In some examples, the one or more external controllers that is/are in wireless communication with the one or more touch sensors **4310** includes one or more respective DSCs.

[0346] Note that the DSCs that are implemented to drive and simultaneously to sense respective one or more signals provided to the one or more external controllers that is/are tethered may be implemented within the one or more external controllers that is/are tethered and/or the element that includes the one or more touch sensors **4310**.

[0347] In general, note that any desired configuration of one or more touch sensors and one or more external controllers including one or more buttons may be implemented and coupled to one or more processing modules via a respective DSCs.

[0348] FIG. **44** is a schematic block diagram of an embodiment **4400** of a touchscreen implemented with one or more touch sensors implemented in touchscreen's bezel the in accordance with the present invention. This diagram shows one or more touch sensors **4410** (e.g., such as in a touchscreen implementation that includes a bezel around at least a portion of the touchscreen).

Different respective configurations are also shown by one or more touch sensors may be implemented within the bezel. Note that the one or more touch sensors within the bezel may be implemented using opaque or non-opaque materials. For example, the one or more sensors implemented within the bezel need not be implemented using transparent conductive materials.

[0349] The bottom of this diagram shows some different respective options (e.g., cross-sections thereof) by which the one or more touch sensors implemented within the bezel may be implemented. For example, the one or more touch sensors implement within the bezel may include an array of buttons driven/sensed by one or more DSCs, a matrix of buttons driven/sensed by one or more DSCs, rows (or columns) of one or more electrodes driven/sensed by one or more DSCs, a matrix of electrodes driven/sensed by one or more DSCs, etc. Note that these different respective options did not compose an exhaustive list. In addition, note the different respective portions of the one or more touch sensors within the bezel may be implemented differently. For example, first portion of the one or more touch sensors within the bezel may be implemented using an array of buttons driven/sensed by one or more DSCs while a second portion of the one or more touch sensors within the bezel may be implemented using rows (or columns) of one or more electrodes driven/sensed by one or more DSCs. In general, any desired combination of different respective implementations of the one or more touch sensors may be included within the bezel.

[0350] FIG. **45** is a schematic block diagram of an embodiment of another embodiment of a method **4500** for execution by one or more devices in accordance with the present invention. The method **4500** operates in step **4510** by transmitting signals to sensors. For example, the sensors may be implemented in any desired format and type including any of the respective examples, embodiments, etc. as described herein.

[0351] The method **4500** operates in step **4520** by detecting signals from the sensors. For example, such detection may include detecting the change of any one or more of the signals that are being transmitted to the sensors. In addition, such detection may include detecting any one or more additional signals that are coupled into the sensors. Note that the operations of the steps **4510** and **4520** may be performed simultaneously. For example, note that the transmitting of the signals to the sensors and detecting of the signals from the sensors may be performed simultaneously. Note that one or more DSCs may be implemented to drive and simultaneously to sense one or more signals provided to the one or more sensors.

[0352] The method **4500** operates in step **4530** by processing the signals from the sensors to generate digital information corresponding to user interaction with one or more of the sensors.

[0353] Also, note that the different respective sensors may correspond to different respective portions of the system. For example, a first sensor may be associated with one or more touch sensors. A second sensor may be associated with a button of an external controller.

[0354] FIG. **46** is a schematic block diagram of an embodiment of another embodiment of a method **4600** for execution by one or more devices in accordance with the present invention. The method **4600** operates in step **4610** by transmitting a first signal to a first sensor of a touchscreen. In addition, the method **4600** operates in step **4620** by detecting change of the first signal to the first sensor of the touchscreen. Note that the operations of the steps **4610** and **4620** may be performed simultaneously. Such operations may be performed using one or more DSCs implemented to drive and simultaneously to sense one or more signals provided to the one or more sensors. The method **4600** operates in step **4630** by processing the change of the first signal to generate digital information corresponding to user interaction with the first sensor of the touchscreen.

[0355] Optionally, any number of additional sensors of the touchscreen may be implemented and similarly operated. For example, the method **4600** operates in step **4612** by transmitting an nth signal to an nth sensor of a touchscreen. In addition, the method **4600** operates in step **4622** by detecting change of the nth signal to the nth sensor of the touchscreen. Note that the operations of the steps **4610** and **4622** may be performed simultaneously. Such operations may be performed using one or more DSCs implemented to drive and simultaneously to sense one or more signals provided to the one or more sensors. The method **4600** operates in step **4632** by processing the change of the nth signal to generate digital information corresponding to user interaction with the nth sensor of the touchscreen.

[0356] The method **4600** also operates in step **4614** by transmitting an n+1th signal to a first sensor of an external controller. In addition, the method **4600** operates in step **4623** by detecting change of the n+1th signal to the first sensor of the external controller. Note that the operations of the steps **4614** and **4624** may be performed simultaneously. Such operations may be performed using one or more DSCs implemented to drive and simultaneously to sense one or more signals provided to the one or more sensors. The method **4600** operates in step **4634** by processing the change of the n+1th signal to generate digital information corresponding to user interaction with the first sensor of the external controller.

[0357] Optionally, any number of additional sensors of the external controller may be implemented and similarly operated. For example, the method **4600** operates in step **4616** by transmitting an xth signal to an xth sensor of an external controller. In addition, the method **4600** operates in step **4626** by detecting change of the xth signal to the xth sensor of the external controller. Note that the operations of the steps **4610** and **4626** may be performed simultaneously. Such operations may be

performed using one or more DSCs implemented to drive and simultaneously to sense one or more signals provided to the one or more sensors. The method **4600** operates in step **4636** by processing the change of the xth signal to generate digital information corresponding to user interaction with the xth sensor of the external controller.

[0358] FIG. **47** is a schematic block diagram of an embodiment **4700** of a radial tire in accordance with the present invention. A vehicle typically includes four tires that are in contact with the road or ground during the vehicle's operation. Certain types of vehicles include more than four tires (e.g., some trucks include two front tires and four rear tires, two on each side, some commercial vehicles include larger numbers of tires sometimes up to 18 tires that are in contact with the road around during the vehicle's operation, etc.).

[0359] A radial tire is a particular type of vehicle entire that includes cord plies that are arranged in one or more directions with respect to the tread of the tire. The right-hand side of the diagram includes a cross-section of radial tire. Generally speaking, within a radial tire, a series of plies of cord reinforces the tire. The network or cords is implemented to give shape and strength to the tire, and that section is oftentimes referred to as the carcass layers. Considering the radial tire from the portion that is in contact with the road, the radial tire includes tread, below which is a belt composed of one or more layers and/or minors, a shoulder strip on the outside of the tire, a sidewall, and a wheel/rim strip. Typically, a bead wire is included within the radial tire near where the tire interfaces with the wheel. In addition, a bead chafer and bead filler may be included above and/or around the bead wire nearby the wheel/rim strip of the tire.

[0360] Referring to a cross-section of the belt of the tire, an x-ply (where x is some positive integer) includes steel belts transverse and/or lengthwise to the tread. In some examples, the belt is composed of the nylon fabric, a steel belt that is transverse to the tread, a steel belt that is lengthwise to the tread, one or more carcass layers, and an inner liner.

[0361] During normal operation of the vehicle, as the tire is rotating, magnetic field is generated from the rotating tire. The one or more steel belts within a radial tire generate a magnetic field as the tire rotates.

[0362] FIG. **48** is a schematic block diagram of an embodiment **4800** of a various degrees of inflation of a tire in accordance with the present invention. This diagram shows various examples of types of inflation with respect to tire. At the top of the diagram, a properly inflated tire will generally maintain uniform tread contact with the road or ground across the entire tread of the tire.

[0363] In the middle of the diagram, an over-inflated tire will generally have tread contact with the road or ground only in the middle portion of the tread (e.g., center tread contact). At the bottom of diagram, an under-inflated tire will generally have tread contact with the road or ground on the outer portions of the tread (e.g., outer tread contact).

[0364] The shape of the tire will be modified based on the amount of error pressure and/or degree of inflation of the tire. In addition, the shape of the one or more steel belts within a radial tire will accordingly be modified based on amount of air pressure and/or degree of inflation of the tire.

[0365] As a tire is rotating and as a magnetic field is being generated by the rotating one or more steel belts of the tire, when there is a change of amount of air pressure and/or degree of inflation of the tire (e.g., based on a puncture, a rupture, flat, loss of air pressure, etc.), then one or more characteristics of the magnetic field will also be changed based on the shape of the tire being changed and the physical displacement of the one or more steel treads and/or bead wire of the tire.

[0366] For example, when the tire has gone flat during the vehicle's motion operation, the one or more steel treads and/or bead wire of the tire will not have a substantially uniform distribution around the center of the wheel. For example, on the bottom of the wheel near the road or ground, the one or more steel treads and/or bead wire of the tire will be in a substantially straight line and relatively closer to the center of the wheel. However, on the side and on the top of the tire, the one or more steel treads and/or bead wire of the tire may still exhibit a substantially uniform distribution around the center of the wheel. This transition from an inflated tire to a flat tire will

result in a modification and change of the magnetic field being generated by the rotating tire. Detection of this modification and change of the magnetic field may be used to determine an adverse condition with respect to the tire.

[0367] A tire pressure monitoring system is implemented using one or more DSCs as described herein in conjunction with one or more devices operative to detect and/or a monitor magnetic fields. Appropriate monitoring of the magnetic field that is generated by radio tire allows for monitoring of the tire and correlating that magnetic field to potential problems with the tire (e.g., puncture, rupture, flat, loss of air pressure, etc.).

[0368] FIG. **49** is a schematic block diagram of an embodiment **4900** of a tire monitoring system in accordance with the present invention. At the top of the diagram, one or more processing modules **4930** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **4930** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **4930**.

[0369] In some examples, a respective DSC **28** is implemented to drive and simultaneously to sense a respective one or more signals provided to a respective electromagnetic/inductive coupler **4925** that is proximate to a radial tire **4910** that includes one or more steel belts. For example, a first DSC **28** is implemented to drive and simultaneously to sense a first respective one or more signals provided to a first electromagnetic/inductive coupler **4925** that is proximate to a radial tire **4910**, and a second DSC **28** is implemented to drive and simultaneously to sense a second respective one or more signals provided to a second electromagnetic/inductive coupler **4925** that is proximate to a radial tire **4910**. Generally speaking note that the one or more electromagnetic/inductive couplers **4925** are implemented in a vehicle chassis domain and the tire **4910** is implemented in the tire domain. The magnetic field that is generated by the one or more steel belts of the tire and/or the bead wire of the tire is coupled from the tire domain to the vehicle chassis domain and particularly into the one or more electromagnetic/inductive couplers **4925**.

[0370] Note that the magnetic field is generated from the rotating tire. The one or more steel treads and/or the bead wire generate one or more magnetic fields in the proximity of the rotating tire. In one example, an appropriately implemented and placed electromagnetic/inductive coupler **4925**, which is driven and simultaneously sensed by DSC **28**, allows for monitoring of the one or more magnetic fields generated by the rotating tire. In another example, appropriately implemented and placed electromagnetic/inductive couplers **4925**, which are driven and simultaneously sensed by DSCs **28**, allow for monitoring of the one or more magnetic fields generated by the rotating tire.

[0371] Regardless of the particular implementation (e.g., a single electromagnetic/inductive coupler **4925** driven and simultaneously sensed by a single DSC **28**, or multiple electromagnetic/inductive coupler **4925** driven and simultaneously sensed by multiple DSCs **28**), the one or more processing modules **4930** is configured to process the signals that are sensed via the one or more DSCs **28** to generate a digital signal that is representative of an electrical characteristic of the one or more electromagnetic/inductive couplers **4925**, which is representative of the magnetic field that is generated by the rotating tire.

[0372] At the bottom left of the diagram, consider that a sinusoid signal is transmitted to a DSC **28** that is coupled to an electromagnetic/inductive coupler **4925**, then when the tire is operating in a steady state mode of operation (e.g., a relatively constant degree of inflation and/or air pressure corresponding to normal tire status), detection of that sinusoidal signal via the DSC **28** is made.

[0373] At the bottom right of the diagram, then when the tire is operating in a non-steady state mode of operation (e.g., abnormal tire status that may be associated to one or more of puncture, rupture, flat, loss of air pressure, etc.), detection of change of that sinusoidal signal via the DSC **28** is made. For example, based upon some type of abnormal tire status, the shape of the tire will change and the magnetic field generated by the rotating one or more steel belts and/or bead wire of the tire will effectuate change of one or more of the electrical characteristics of the

electromagnetic/inductive coupler **4925**. Note that the change of that sinusoidal signal via the DSC **28** may be manifested in any of a number of ways including a change of PC component, oscillating magnitude, phase, frequency, and/or any other parameter associated with signal that is driven the DSC **28** and simultaneously sensed there from.

[0374] FIG. **50** is a schematic block diagram of another embodiment **5000** of a tire monitoring system in accordance with the present invention. This diagram shows the tire rotating and the magnetic fields generated therefrom. An axle, braking mechanism, etc. couples the wheel to the vehicle chassis. The tire is mounted to the wheel.

[0375] As the tire rotates, a magnetic field is generated by the rotating one or more steel belts and/or bead wire of the tire. This magnetic field will effectuate change of one or more of the electrical characteristics of the electromagnetic/inductive coupler **4925**. One or more electromagnetic/inductive couplers **5020** is arranged in any desired configuration to facilitate monitoring of the magnetic field that is generated by the rotating tire. For example, electromagnetic/inductive couplers **5020** may be arranged in a straight line (e.g., one dimensional space, 1-D) on the vehicle chassis to monitor the magnetic field is generated by the rotating tire. Alternatively, electromagnetic/inductive couplers **5020** may be arranged in a planar array (e.g., two dimensional space, 2-D) on the vehicle chassis to monitor the magnetic field is generated by the rotating tire. In even another embodiment, electromagnetic/inductive couplers **5020** may be arranged in any three-dimensional configuration (e.g., three dimensional space, 3-D) on the vehicle chassis to monitor the magnetic field is generated by the rotating tire.

[0376] FIG. **51** is a schematic block diagram of an embodiment **5100** of tire profile monitoring in accordance with the present invention. As mentioned above, one or more electromagnetic/inductive couplers may be arranged in any desired configuration (e.g., 1-D space, 2-D space, 3-D space) on the vehicle chassis to monitor the magnetic field is generated by the rotating tire.

[0377] In a multiple electromagnetic/inductive coupler implementation, a tire profile that is associated with the magnetic field generated by the rotating tire may be generated at different respective times. For example, a tire profile **1** is generated at the time 1, a tire profile **2** is generated at the time 2, etc.

[0378] One or more processing modules is configured to process signals coupled from one or more DSCs that are based on one or more electromagnetic/inductive couplers to generate one or more tire profiles associated with the magnetic field is generated by the rotating tire. For example, consider an implementation that includes 4 electromagnetic/inductive couplers. A tire profile **1** is generated at the time 1 that is based on measurements associated with those 4 electromagnetic/inductive couplers. Similarly, a tire profile **2** is generated at the time 2 that is based on measurements associated with those 4 electromagnetic/inductive couplers. Generally speaking, this process may be performed any number of times up to n, where n is a positive integer.

[0379] As the shape of the tire changes, the magnetic field being generated by the rotating tire will also change. Detection of changes of the tire profile at different times (e.g., a delta or the difference a between the tire profile **1** at time 1 and the tire profile **2** at time 2, and/or a delta or the difference b between the tire profile **2** at time 2 and the tire profile n at time n) allows for identification of an adverse condition with respect to the tire (e.g., puncture, rupture, flat, loss of air pressure, etc.).

[0380] In addition, note that a single electromagnetic/inductive coupler **5020** may alternatively be implemented on the vehicle chassis to monitor the magnetic field is generated by the rotating tire. Instead of generating a higher profile that includes multiple measurements associated with multiple electromagnetic/inductive couplers, a single measurement associated with a single electromagnetic/inductive coupler is used. Similarly, detection of changes of that measurement at different times may be used for identification of an adverse condition with respect to the tire (e.g., puncture, rupture, flat, loss of air pressure, etc.).

[0381] FIG. **52** is a schematic block diagram of another embodiment **5200** of a tire monitoring system in accordance with the present invention. In this diagram, one or more sensors **5240** is

associated with the tire. For example, the one or more sensors **5240** may be implemented within one or more liners associated with the tire.

[0382] At the top of the diagram are examples of liners that include one or more sensors within a tire. Note that a liner may be implemented within the inner lining of a tire, integrated into the tire built, installed during tire mounting, etc. and/or otherwise associated with and/or implemented with the tire. Note that any desired implementation of sensors may be implemented within the one or more liners associated with the tire. For example, different liners may be implemented based on different patterns inside of the tire such as based on a mesh, matrix of sensors, one or more electrodes in a first direction (e.g., around tire, start/end), one or more electrodes in two directions. For example, considering some possible cross-sections of sensors include an array of sensors driven/sensed by one or more DSCs, a matrix of sensors driven/sensed by one or more DSCs, one or more rows (or columns) of electrodes/sensors driven/sensed by one or more DSCs, a matrix of electrodes sensors driven/sensed by one or more DSCs, etc.

[0383] One or more processing modules **5240** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **5240** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **5240**. A DSC **28** is implemented to drive and simultaneously to sense one or more signals provided to one of the one or more sensors **5230**.

[0384] When there is a change of amount of air pressure and/or degree of inflation of the tire (e.g., based on a puncture, a rupture, flat, loss of air pressure, etc.) and/or an actual physical modification of one or more of the sensors implemented within the one or more liners associated with the tire (e.g., based on a puncture, a rupture, flat, etc.), the one or more DSCs **28** will detect, based on a change of electrical characteristic of one or more of the sensors, an adverse condition with respect to the tire.

[0385] In addition, one or more energy harvesters **5210** is implemented within the tire and/or wheel. The tire includes one or more energy harvesters **5210** to energize (e.g., drive/sense) the one or more sensors within the tire.

[0386] Examples of energy harvester including any one or more of the following: photovoltaic: generating electric power by converting photon irradiation such as solar iteration into electricity, piezoelectric effect: converts mechanical strain into electric current or voltage, pyroelectric: pyroelectric effect converts a temperature change into electric current or voltage (e.g., analogous to the piezoelectric effect, which is another type of ferroelectric behavior), thermoelectrics: a thermal gradient formed between two dissimilar conductors produces a voltage, electrostatic (capacitive): changing capacitance of vibration-dependent capacitors (e.g., vibrations separate the plates of a charged variable capacitor, and mechanical energy is converted into electrical energy), magnetic induction: magnets wobbling on a cantilever are sensitive to even small vibrations and generate microcurrents by moving relative to conductors due to Faraday's law of induction (e.g., the kinetic/rotational energy of the rotating tire baby converted into electrical energy using magnetic induction). Note that these examples do not compose an exhaustive list and other forms of energy harvesting may be implemented.

[0387] Within the tire, the one or more energy harvesters **5210** provides electric energy that is stored in one or more energy storage elements **5220**. A non-exhaustive list of examples of the one or more energy storage elements **5220** include a capacitor, a battery, etc. The one or more energy storage elements **5220** provides energy to the one or more processing modules **5240**, the one or more DSCs **28**, and one or more communication modules **5250**. The one or more communication modules **5250** is configured to perform communication to and from one or more other communication modules associated with the vehicle chassis that are also in communication with one or more other processing modules implemented to process the signals provided from the tire to identify an adverse condition with respect to the tire. For example, such communication may be performed wirelessly, via electromagnetic (EM) induction, near-field communication (NFC), etc.,

and/or other means.

[0388] FIG. **53** is a schematic block diagram of another embodiment **5300** of a tire monitoring system in accordance with the present invention. This diagram shows one possible implementation by which communication from one or more devices within the tire is communicated to one or more devices within the vehicle chassis.

[0389] One or more energy harvesters **5310** is implemented to generate energy that is stored in one or more energy storage elements **5320**. One or more processing modules **28**, one or more communication modules **5350**, and one or more DSCs are powered and/or energized by the energy from the one or more energy storage elements **5320**. In addition, one or more sensors **5330** are implemented within tire. As described herein, any number of different limitations may be used by which the one or more sensors **5330** are implemented within the tire. For example, they may be implemented within one or more liners within the tire.

[0390] The one or more processing modules **5340** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **5340** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **5340**. A DSC **28** is implemented to drive and simultaneously to sense one or more signals provided to one of the one or more sensors **5330**.

[0391] The one or more communication modules **5370** is configured to support communications with one or more other communication modules **5360** that are implemented within the vehicle chassis domain. In addition, one or more other processing modules **5370** is coupled to the one or more communication modules **5370**. Note that the one or more processing modules **5370** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **5370**. The one or more processing modules **5370** is configured to interact with and or communicate with any one or more other system, device, module, circuitry, component, etc. within the vehicle.

[0392] Note also that the elements within this diagram may be viewed as being implemented in a vehicle chassis domain or a tire domain. For example, the one or more elements within the tire may be viewed as being implemented within the tire domain, and the one or more elements within the vehicle may be viewed as being within the vehicle chassis domain. Also, note that the communication between the one or more communication modules **5350** and **5360** may be performed in accordance with number of different means (e.g., wirelessly, via electromagnetic (EM) induction, near-field communication (NFC), etc., and/or other means).

[0393] FIG. **54** is a schematic block diagram of another embodiment **5400** of a tire monitoring system in accordance with the present invention. This diagram shows one possible implementation by which communication from one or more devices within the tire is communicated to one or more devices within the vehicle chassis.

[0394] One or more energy harvesters **5410** is implemented to generate energy that is stored in one or more energy storage elements **5420**. One or more processing modules **28**, one or more communication modules **5450**, and one or more DSCs are powered and/or energized by the energy from the one or more energy storage elements **5420**. In addition, one or more sensors **5430** are implemented within tire. As described herein, any number of different limitations may be used by which the one or more sensors **5430** are implemented within the tire. For example, they may be implemented within one or more liners within the tire.

[0396] The one or more processing modules **5440** is coupled to drive-sense circuits (DSCs) **28**. Note that the one or more processing modules **5440** may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules **5440**. A DSC **28** and a first one or more DSCs **28** is implemented to drive and simultaneously to sense one or more signals provided to one of the one or more sensors **5430**. A DSC **28** in a second one or more DSCs **28** is implemented to drive and simultaneously to sense one or more signals provided to one of the one or more

electromagnetic/inductive couplers 5425 implemented within the tire domain.

[0397] Communication is performed between one or more electromagnetic/inductive couplers 5425 implemented within the tire domain and another one or more electromagnetic/inductive couplers 5425 implemented within the vehicle chassis domain. In addition, one or more other processing modules 5470 is coupled to the second one or more DSCs 28 is implemented to drive and simultaneously to sense one or more signals provided to one of the one or more electromagnetic/inductive couplers 5425 implemented within the vehicle chassis domain.

[0398] Note that the one or more processing modules 5470 may include integrated memory and/or be coupled to other memory. At least some of the memory stores operational instructions to be executed by the one or more processing modules 5470. The one or more processing modules 5470 is configured to interact with and or communicate with any one or more other system, device, module, circuitry, component, etc. within the vehicle.

[0399] In addition, note that the signals communicated between the respective first one or more DSCs 28 implemented within the tire domain and the second one or more DSCs 28 implemented within the vehicle chassis domain are not only based on information related to the one or more touch sensors 5430 that are associated with the tire, but they may also include information related to the magnetic field generated from a rotating tire. For example, from the rotating one or more steel belts and/or bead wire of the tire. Note that the second one or more DSCs 28 implemented within the vehicle chassis domain are capable not only to detect signals via the one or more electromagnetic/inductive couplers 5425 implemented within the tire and vehicle chassis domains, but are also capable to detect any signal that is coupled into the one or more electromagnetic/inductive couplers 5425 implemented within the tire and vehicle chassis domains.

[0400] This diagram particularly shows communication between the tire domain in the vehicle chassis domain being performed based on electromagnetic (EM) induction. Note also that the communication between the communication between the tire domain in the vehicle chassis domain may alternatively be performed in accordance with number of different means (e.g., wirelessly, near-field communication (NFC), etc., and/or other means).

[0401] It is noted that terminologies as may be used herein such as bit stream, stream, signal sequence, etc. (or their equivalents) have been used interchangeably to describe digital information whose content corresponds to any of a number of desired types (e.g., data, video, speech, text, graphics, audio, etc. any of which may generally be referred to as 'data').

[0402] As may be used herein, the terms "substantially" and "approximately" provide an industry-accepted tolerance for its corresponding term and/or relativity between items. For some industries, an industry-accepted tolerance is less than one percent and, for other industries, the industry-accepted tolerance is 10 percent or more. Other examples of industry-accepted tolerance range from less than one percent to fifty percent. Industry-accepted tolerances correspond to, but are not limited to, component values, integrated circuit process variations, temperature variations, rise and fall times, thermal noise, dimensions, signaling errors, dropped packets, temperatures, pressures, material compositions, and/or performance metrics. Within an industry, tolerance variances of accepted tolerances may be more or less than a percentage level (e.g., dimension tolerance of less than $\pm 1\%$). Some relativity between items may range from a difference of less than a percentage level to a few percent. Other relativity between items may range from a difference of a few percent to magnitude of differences.

[0403] As may also be used herein, the term(s) "configured to", "operably coupled to", "coupled to", and/or "coupling" includes direct coupling between items and/or indirect coupling between items via an intervening item (e.g., an item includes, but is not limited to, a component, an element, a circuit, and/or a module) where, for an example of indirect coupling, the intervening item does not modify the information of a signal but may adjust its current level, voltage level, and/or power level. As may further be used herein, inferred coupling (i.e., where one element is coupled to

another element by inference) includes direct and indirect coupling between two items in the same manner as “coupled to”.

[0404] As may even further be used herein, the term “configured to”, “operable to”, “coupled to”, or “operably coupled to” indicates that an item includes one or more of power connections, input(s), output(s), etc., to perform, when activated, one or more its corresponding functions and may further include inferred coupling to one or more other items. As may still further be used herein, the term “associated with”, includes direct and/or indirect coupling of separate items and/or one item being embedded within another item.

[0405] As may be used herein, the term “compares favorably”, indicates that a comparison between two or more items, signals, etc., provides a desired relationship. For example, when the desired relationship is that signal **1** has a greater magnitude than signal **2**, a favorable comparison may be achieved when the magnitude of signal **1** is greater than that of signal **2** or when the magnitude of signal **2** is less than that of signal **1**. As may be used herein, the term “compares unfavorably”, indicates that a comparison between two or more items, signals, etc., fails to provide the desired relationship.

[0406] As may be used herein, one or more claims may include, in a specific form of this generic form, the phrase “at least one of a, b, and c” or of this generic form “at least one of a, b, or c”, with more or less elements than “a”, “b”, and “c”. In either phrasing, the phrases are to be interpreted identically. In particular, “at least one of a, b, and c” is equivalent to “at least one of a, b, or c” and shall mean a, b, and/or c. As an example, it means: “a” only, “b” only, “c” only, “a” and “b”, “a” and “c”, “b” and “c”, and/or “a”, “b”, and “c”.

[0407] As may also be used herein, the terms “processing module”, “processing circuit”, “processor”, “processing circuitry”, and/or “processing unit” may be a single processing device or a plurality of processing devices. Such a processing device may be a microprocessor, micro-controller, digital signal processor, microcomputer, central processing unit, field programmable gate array, programmable logic device, state machine, logic circuitry, analog circuitry, digital circuitry, and/or any device that manipulates signals (analog and/or digital) based on hard coding of the circuitry and/or operational instructions. The processing module, module, processing circuit, processing circuitry, and/or processing unit may be, or further include, memory and/or an integrated memory element, which may be a single memory device, a plurality of memory devices, and/or embedded circuitry of another processing module, module, processing circuit, processing circuitry, and/or processing unit. Such a memory device may be a read-only memory, random access memory, volatile memory, non-volatile memory, static memory, dynamic memory, flash memory, cache memory, and/or any device that stores digital information. Note that if the processing module, module, processing circuit, processing circuitry, and/or processing unit includes more than one processing device, the processing devices may be centrally located (e.g., directly coupled together via a wired and/or wireless bus structure) or may be distributedly located (e.g., cloud computing via indirect coupling via a local area network and/or a wide area network). Further note that if the processing module, module, processing circuit, processing circuitry and/or processing unit implements one or more of its functions via a state machine, analog circuitry, digital circuitry, and/or logic circuitry, the memory and/or memory element storing the corresponding operational instructions may be embedded within, or external to, the circuitry comprising the state machine, analog circuitry, digital circuitry, and/or logic circuitry. Still further note that, the memory element may store, and the processing module, module, processing circuit, processing circuitry and/or processing unit executes, hard coded and/or operational instructions corresponding to at least some of the steps and/or functions illustrated in one or more of the Figures. Such a memory device or memory element can be included in an article of manufacture.

[0408] One or more embodiments have been described above with the aid of method steps illustrating the performance of specified functions and relationships thereof. The boundaries and sequence of these functional building blocks and method steps have been arbitrarily defined herein

for convenience of description. Alternate boundaries and sequences can be defined so long as the specified functions and relationships are appropriately performed. Any such alternate boundaries or sequences are thus within the scope and spirit of the claims. Further, the boundaries of these functional building blocks have been arbitrarily defined for convenience of description. Alternate boundaries could be defined as long as the certain significant functions are appropriately performed. Similarly, flow diagram blocks may also have been arbitrarily defined herein to illustrate certain significant functionality.

[0409] To the extent used, the flow diagram block boundaries and sequence could have been defined otherwise and still perform the certain significant functionality. Such alternate definitions of both functional building blocks and flow diagram blocks and sequences are thus within the scope and spirit of the claims. One of average skill in the art will also recognize that the functional building blocks, and other illustrative blocks, modules and components herein, can be implemented as illustrated or by discrete components, application specific integrated circuits, processors executing appropriate software and the like or any combination thereof.

[0410] In addition, a flow diagram may include a “start” and/or “continue” indication. The “start” and “continue” indications reflect that the steps presented can optionally be incorporated in or otherwise used in conjunction with one or more other routines. In addition, a flow diagram may include an “end” and/or “continue” indication. The “end” and/or “continue” indications reflect that the steps presented can end as described and shown or optionally be incorporated in or otherwise used in conjunction with one or more other routines. In this context, “start” indicates the beginning of the first step presented and may be preceded by other activities not specifically shown. Further, the “continue” indication reflects that the steps presented may be performed multiple times and/or may be succeeded by other activities not specifically shown. Further, while a flow diagram indicates a particular ordering of steps, other orderings are likewise possible provided that the principles of causality are maintained.

[0411] The one or more embodiments are used herein to illustrate one or more aspects, one or more features, one or more concepts, and/or one or more examples. A physical embodiment of an apparatus, an article of manufacture, a machine, and/or of a process may include one or more of the aspects, features, concepts, examples, etc. described with reference to one or more of the embodiments discussed herein. Further, from figure to figure, the embodiments may incorporate the same or similarly named functions, steps, modules, etc. that may use the same or different reference numbers and, as such, the functions, steps, modules, etc. may be the same or similar functions, steps, modules, etc. or different ones.

[0412] Unless specifically stated to the contra, signals to, from, and/or between elements in a figure of any of the figures presented herein may be analog or digital, continuous time or discrete time, and single-ended or differential. For instance, if a signal path is shown as a single-ended path, it also represents a differential signal path. Similarly, if a signal path is shown as a differential path, it also represents a single-ended signal path. While one or more particular architectures are described herein, other architectures can likewise be implemented that use one or more data buses not expressly shown, direct connectivity between elements, and/or indirect coupling between other elements as recognized by one of average skill in the art.

[0413] The term “module” is used in the description of one or more of the embodiments. A module implements one or more functions via a device such as a processor or other processing device or other hardware that may include or operate in association with a memory that stores operational instructions. A module may operate independently and/or in conjunction with software and/or firmware. As also used herein, a module may contain one or more sub-modules, each of which may be one or more modules.

[0414] As may further be used herein, a computer readable memory includes one or more memory elements. A memory element may be a separate memory device, multiple memory devices, or a set of memory locations within a memory device. Such a memory device may be a read-only memory,

random access memory, volatile memory, non-volatile memory, static memory, dynamic memory, flash memory, cache memory, and/or any device that stores digital information. The memory device may be in a form a solid-state memory, a hard drive memory, cloud memory, thumb drive, server memory, computing device memory, and/or other physical medium for storing digital information.

[0415] While particular combinations of various functions and features of the one or more embodiments have been expressly described herein, other combinations of these features and functions are likewise possible. The present disclosure is not limited by the particular examples disclosed herein and expressly incorporates these other combinations.

Claims

1. A touch sensor system comprising: a touch sensor; a drive-sense circuit (DSC) operably coupled to the touch sensor, wherein, when enabled, the DSC is configured to: drive a first signal via a single line coupling to the touch sensor and simultaneously sense, via the single line, change of the first signal that is based on a second signal coupled to the touch sensor from a non-permitted user of the touch sensor system; and process the first signal to generate a digital signal that is representative of the change of the first signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system; memory that stores operational instructions; and a processing module operably coupled to the DSC and to the memory, wherein, when enabled, the processing module is configured to execute the operational instructions to: process the digital signal to determine the change of the first signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system; and detect interaction of the non-permitted user with the touch sensor based on the change of the first signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system; and block the interaction of the non-permitted user with the touch sensor.
2. The touch sensor system of claim 1, wherein: the change of the first signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system changes an electrical characteristic of the touch sensor.
3. The touch sensor system of claim 1, wherein, when enabled, the processing module is configured to execute the operational instructions to: block the interaction of the non-permitted user with the touch sensor including to abort execution of one or more operations associated with the interaction of the non-permitted user with the touch sensor.
4. The touch sensor system of claim 1, wherein the second signal is uniquely associated with the non-permitted user.
5. The touch sensor system of claim 1, wherein, when enabled, the DSC is further configured to: drive the first signal via the single line coupling to the touch sensor and simultaneously sense, via the single line, change of the first signal that is also based on a third signal coupled to the touch sensor from an authorized user of the touch sensor system.
6. The touch sensor system of claim 5, wherein: the change of the first signal that is also based on the third signal coupled to the touch sensor from the authorized user of the touch sensor system changes an electrical characteristic of the touch sensor.
7. The touch sensor system of claim 6, wherein, when enabled, the processing module is configured to execute the operational instructions to: process the digital signal to determine the change of the first signal that is based on the third signal coupled to the touch sensor from the authorized user of the touch sensor system; detect interaction of the authorized user with the touch sensor based on the change of the first signal that is based on the third signal coupled to the touch sensor from the authorized user of the touch sensor system; and facilitate execution of one or more operations associated with other interaction of the authorized user with the touch sensor while blocking the interaction of the non-permitted user with the touch sensor.

8. The touch sensor system of claim 7, wherein: the touch sensor system includes an in vehicle display within a vehicle; the non-permitted user with the touch sensor is a driver of the vehicle; and the authorized user of the touch sensor system is a passenger of the vehicle.
9. The touch sensor system of claim 1 further comprising: another DSC, wherein, when enabled, the another DSC is configured to couple the second signal from the non-permitted user of the touch sensor system via a DSC interface.
10. The touch sensor system of claim 9, wherein the DSC interface includes at least one of a pen, an e-pen, a conductive mat, a seat, a seat belt, a cell phone, a smart phone, a key fob, a watch, an active wrist-band, a personal digital assistant (PDA), or a clip-on element.
11. The touch sensor system of claim 1, wherein touch sensor device includes a touchscreen, a pad device, a laptop, a cell phone, a smartphone, a whiteboard, an interactive display, a navigation system display, or an in vehicle display.
12. The touch sensor system of claim 1, wherein the touch sensor system includes at least one of: a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, or an array of buttons.
13. The touch sensor system of claim 1, wherein: the first signal includes a first frequency; and the second signal includes a second frequency that is different than the first frequency.
14. The touch sensor system of claim 1, wherein the second signal includes an Identifier (ID) code that is uniquely associated with the non-permitted user of the touch sensor system, and wherein, when enabled, the processing module is further configured to execute the operational instructions to process the ID code of the digital signal to identify the non-permitted user of the touch sensor system.
15. The touch sensor system of claim 1, wherein the DSC further comprises: a power source circuit operably coupled to the touch sensor via the single line, wherein, when enabled, the power source circuit is configured to provide the first signal that includes an analog signal via the single line coupling to the touch sensor, and wherein the analog signal includes at least one of a DC (direct current) component or an oscillating component; and a power source change detection circuit operably coupled to the power source circuit, wherein, when enabled, the power source change detection circuit is configured to: detect an effect on the analog signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system; and digital signal that is representative of the change of the first signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system.
16. The touch sensor system of claim 15 further comprising: the power source circuit including a power source to source at least one of a voltage or a current to the touch sensor via the single line; and the power source change detection circuit including: a power source reference circuit configured to provide at least one of a voltage reference or a current reference; and a comparator configured to compare the at least one of the voltage or the current provided to the touch sensor to the at least one of the voltage reference or the current reference in accordance with producing the analog signal.
17. A touch sensor system comprising: a touch sensor; a drive-sense circuit (DSC) operably coupled to the touch sensor, wherein, when enabled, the DSC is configured to: drive a first signal via a single line coupling to the touch sensor and simultaneously sense, via the single line, change of the first signal that is based on a second signal coupled to the touch sensor from a non-permitted user of the touch sensor system, wherein the second signal is uniquely associated with the non-permitted user, and wherein the touch sensor system includes at least one of a touchscreen, a button, an electrode, an external controller, rows of electrodes, columns of electrodes, a matrix of buttons, or an array of buttons; and process the first signal to generate a digital signal that is representative of the change of the first signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system; memory that stores operational instructions; and a processing module operably coupled to the DSC and to the memory,

wherein, when enabled, the processing module is configured to execute the operational instructions to: process the digital signal to determine the change of the first signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system; and detect interaction of the non-permitted user with the touch sensor based on the change of the first signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system; and block the interaction of the non-permitted user with the touch sensor.

18. The touch sensor system of claim 17 further comprising: another DSC, wherein, when enabled, the another DSC is configured to couple the second signal from the non-permitted user of the touch sensor system via a DSC interface.

19. The touch sensor system of claim 17, wherein the DSC further comprises: a power source circuit operably coupled to the touch sensor via the single line, wherein, when enabled, the power source circuit is configured to provide the first signal that includes an analog signal via the single line coupling to the touch sensor, and wherein the analog signal includes at least one of a DC (direct current) component or an oscillating component; and a power source change detection circuit operably coupled to the power source circuit, wherein, when enabled, the power source change detection circuit is configured to: detect an effect on the analog signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system; and digital signal that is representative of the change of the first signal that is based on the second signal coupled to the touch sensor from the non-permitted user of the touch sensor system.

20. The touch sensor system of claim 19 further comprising: the power source circuit including a power source to source at least one of a voltage or a current to the touch sensor via the single line; and the power source change detection circuit including: a power source reference circuit configured to provide at least one of a voltage reference or a current reference; and a comparator configured to compare the at least one of the voltage or the current provided to the touch sensor to the at least one of the voltage reference or the current reference in accordance with producing the analog signal.
