

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413785
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Deng; Zhipin et al.

Signalling of general constraints flag

Abstract

Methods, systems, apparatus for video processing are described. The processing may include encoding, decoding or transcoding. One example video processing method includes performing a conversion between a video and a bitstream of the video according to a rule. The rule specifies that a syntax element is included in a profile, tier, level information syntax structure to indicate whether one or more general constraint information syntax elements are included in a general constraint information syntax structure and/or whether the general constraint information syntax structure is included in the profile, tier, level information syntax structure.

Inventors: Deng; Zhipin (Beijing, CN), Wang; Ye-kui (San Diego, CA), Zhang; Li (San Diego, CA), Zhang; Kai (San Diego, CA)

Applicant: Beijing Bytedance Network Technology Co., Ltd. (Beijing, CN); Bytedance Inc. (Los Angeles, CA)

Family ID: 78707743

Assignee: BEIJING BYTEDANCE NETWORK TECHNOLOGY CO., LTD. (Beijing, CN); BYTEDANCE INC. (Los Angeles, CA)

Appl. No.: 18/517139

Filed: November 22, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240129540 A1	Apr. 18, 2024

Foreign Application Priority Data

WO	PCT/CN2020/091740	May. 22, 2020
----	-------------------	---------------

Related U.S. Application Data

continuation parent-doc US 17992270 20221122 US 11956474 child-doc US 18517139
continuation parent-doc WO PCT/CN2021/095386 20210524 PENDING child-doc US 17992270

Publication Classification

Int. Cl.: H04N19/70 (20140101); H04N19/169 (20140101); H04N19/174 (20140101); H04N19/186 (20140101); H04N19/46 (20140101)

U.S. Cl.:

CPC H04N19/70 (20141101); H04N19/174 (20141101); H04N19/186 (20141101); H04N19/188 (20141101); H04N19/46 (20141101);

Field of Classification Search

CPC: H04N (19/70); H04N (19/174)

USPC: 375/240.26

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5983022	12/1998	Watkins	N/A	N/A
11956474	12/2023	Deng et al.	N/A	N/A
2013/0114718	12/2012	Lu	N/A	N/A
2015/0103888	12/2014	Chen	N/A	N/A
2015/0195561	12/2014	Wang	N/A	N/A
2015/0264099	12/2014	Deshpande	N/A	N/A
2015/0373348	12/2014	Wang	N/A	N/A
2016/0366428	12/2015	Deshpande	N/A	N/A
2017/0094277	12/2016	Chen	N/A	N/A
2017/0214938	12/2016	Zhang	N/A	N/A
2018/0041762	12/2017	Ikai	N/A	N/A
2019/0037250	12/2018	Tsukagoshi	N/A	N/A
2019/0132612	12/2018	Deshpande	N/A	N/A
2019/0141318	12/2018	Li	N/A	N/A
2019/0208212	12/2018	Horowitz	N/A	N/A
2020/0107027	12/2019	He	N/A	N/A
2020/0154144	12/2019	Deshpande	N/A	N/A
2020/0260070	12/2019	Yoo	N/A	N/A
2021/0014535	12/2020	Rusanovskyy	N/A	N/A
2021/0203996	12/2020	Hsiang	N/A	N/A
2021/0268207	12/2020	Hatton et al.	N/A	N/A
2021/0321130	12/2020	Li	N/A	N/A
2021/0329303	12/2020	Deshpande	N/A	H04N 19/70
2021/0368207	12/2020	Li	N/A	N/A
2022/0103866	12/2021	Bossen	N/A	N/A
2022/0132107	12/2021	Paluri	N/A	N/A
2022/0141495	12/2021	Kim	N/A	N/A
2022/0264136	12/2021	Chen	N/A	N/A
2022/0385903	12/2021	Yoo	N/A	N/A
2022/0394301	12/2021	Deshpande	N/A	N/A
2023/0171432	12/2022	Rosewarne	N/A	N/A
2023/0188757	12/2022	Naser et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
103688547	12/2013	CN	N/A
105594209	12/2015	CN	N/A
105981387	12/2015	CN	N/A
106170981	12/2015	CN	N/A
106664447	12/2016	CN	N/A
107105295	12/2016	CN	N/A
110506420	12/2018	CN	N/A
110896486	12/2019	CN	N/A
3051486	12/2015	EP	N/A
554039	12/2023	IN	N/A
2007243427	12/2006	JP	N/A
7415043	12/2023	JP	N/A
7540871	12/2023	JP	N/A
7597477	12/2023	JP	N/A
7601494	12/2023	JP	N/A
202007167	12/2019	TW	N/A
2013159335	12/2012	WO	N/A
2014008290	12/2013	WO	N/A
2015138979	12/2014	WO	N/A
2019188097	12/2018	WO	N/A
2020038465	12/2019	WO	N/A
2020076069	12/2019	WO	N/A
2021207023	12/2020	WO	N/A

OTHER PUBLICATIONS

Japanese Office Action from Japanese Patent Application No. 2023-190717 dated Jul. 9, 2024, 6 pages. cited by applicant

Document: JVET-Q2001-v5, Bross, B., et al., “Versatile Video Coding (Draft 8),” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 492 pages. cited by applicant

Document: JVET-O0417-v1, Bordes, P., et al., “AHG17: On general constraint information,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 15th Meeting: Gothenburg, SE, Jul. 3-12, 2019, 3 pages. cited by applicant

Document: JVET-P0486, Sarwer, M., et al., “CE8-related: Alignment of maximum transform-skip size with maximum transform block size,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 16th Meeting: Geneva, CH, Oct. 1-11, 2019, 10 pages. cited by applicant
Extended European Search Report from European Application No. 23212823.1 dated Feb. 16, 2024, 9 pages. cited by applicant

Japanese Office Action from Japanese Application No. 202257110 dated Feb. 20, 2024, 6 pages. With English Translation. cited by applicant

Final Office Action from U.S. Appl. No. 17/994,864 dated Apr. 17, 2024, 21 pages. cited by applicant
Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/095386, English Translation of International Search Report dated Aug. 23, 2021, 11 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/095387, English Translation of International Search Report dated Aug. 24, 2021, 9 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/095388, English Translation of International Search Report dated Aug. 24, 2021, 9 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No.

PCT/CN2021/095389, English Translation of International Search Report dated Aug. 31, 2021, 10 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/096592, English Translation of International Search Report dated Sep. 2, 2021, 11 pages. cited by applicant

Non-Final Office Action dated Jan. 24, 2023, 22 pages, U.S. Appl. No. 17/898,051, filed Aug. 29, 2022. cited by applicant

Foreign Communication From A Related Counterpart Application, Indian Application No. 202227067001, Indian Office Action dated Jan. 24, 2023, 6 pages. cited by applicant

Notice of Allowance dated Jan. 18, 2023, 32 pages, U.S. Appl. No. 17/898,073, filed Aug. 29, 2022. cited by applicant

Non-Final Office Action dated May 22, 2023, 29 pages, U.S. Appl. No. 17/965,590, filed Oct. 13, 2022. cited by applicant

Non-Final Office Action dated Apr. 11, 2023, 25 pages, U.S. Appl. No. 17/994,864, filed Nov. 28, 2022. cited by applicant

Non-Final Office Action dated May 18, 2023, 19 pages, U.S. Appl. No. 17/897,943, filed Aug. 29, 2022. cited by applicant

Foreign Communication From a Related Counterpart Application, European Application No. 21760362.0, Extended European Search Report dated Jun. 28, 2023, 8 pages. cited by applicant

Extended European Search Report from European Application No. 21808251.9 dated Feb. 1, 2024, 16 pages. cited by applicant

Extended European Search Report from European Application No. 21787637.4 dated Jul. 18, 2023, 17 pages. cited by applicant

Partial Supplementary European Search Report from European Application No. 21808251.9 dated Sep. 26, 2023, 14 pages. cited by applicant

Extended European Search Report from European Application No. 21787637.4 dated Oct. 25, 2023, 18 pages. cited by applicant

Non-Final Office Action dated Apr. 27, 2023, 24 pages, U.S. Appl. No. 17/992,270, filed Nov. 22, 2022. cited by applicant

Non-Final Office Action dated Dec. 20, 2023, 20 pages, U.S. Appl. No. 17/994,864, filed Nov. 28, 2022. cited by applicant

Document: JVET-Q2001-vE, Bross, B., et al., “Versatile Video Coding (Draft 8),” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 512 pages. cited by applicant

Information technology—High efficiency coding and media delivery in heterogeneous environments—Part 2: High Efficiency Video Coding1, ISO/IEC JTC 1/SC 29/WG 11 N17661, Rec. ITU-T H.265 | ISO/IEC 23008-2 (in force edition), Apr. 20, 2018, 8 pages. cited by applicant

Document: JVET-G1001-v1, Chen, J., et al., “Algorithm description of Joint Exploration Test Model 7 (JEM7),” Joint Video Exploration Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 7th Meeting: Torino, IT, Jul. 13-21, 2017, 50 pages. cited by applicant

Document: JVET-Q2002-v3, Chen J., et al., “Algorithm description for Versatile Video Coding and Test Model 8 (VTM 8),” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 97 pages. cited by applicant

Li, X., Retrieved from the Internet: https://vcgit.hhi.fraunhofer.de/jvetAA/CSoftware_VTM.git, VTM software, Nov. 2, 2022, 3 pages. cited by applicant

JVET-R2001-vB, Bross, B., et al., “Versatile Video Coding (Draft 9),” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 530 pages. cited by applicant

Jvet-N0276, Boyce, J., “AHG15: On interoperability point signalling,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 14th Meeting: Geneva, CH, Mar. 19-27, 2019, 16 pages. cited by applicant

JVET-P0117-v3, Wang, Y.K., “AHG8: Scalability—PTL and decoder capability,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 16th Meeting: Geneva, CH, Oct.

1-11, 2019, 6 pages. cited by applicant

JVET-Q0781-v1, Xu, X., et al., “AHG 9: On conditioning the presence of inter-/intra-related syntax elements in PH,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 3 pages. cited by applicant

JVET-Q0428-V3, Xu, X., et al., “AHG 9: Picture header syntax cleanups,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 10 pages. cited by applicant

JVET-O1076-V4, Wang, Y.K., et al., Report of BoG on high-level syntax Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 15th Meeting: Gothenburg, SE, Jul. 3-12, 2019, 50 pages. cited by applicant

JVET-R0113, Samuelsson, J., et al., “AHG9: On Picture Parameter Set,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 3 pages. cited by applicant

JVET-R0202, Laroche, G., et al., “AHG9: Syntax cleanups when Picture Header is in the Slice Header,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 6 pages. cited by applicant

JVET-R0073-v1, Deng, Z., et al., “AHG9: Some cleanups on QP delta signalling,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 7 pages. cited by applicant

JVET-Q0505, Zhang, H., et al., “AHG15: Improvement for Quantization Matrix Signaling,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 9 pages. cited by applicant

JVET-R0301-v1, Li, L., et al., “AHG12: on scaling list chroma present flag in APS,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 5 pages. cited by applicant

JVET-R0177, Naser, K., et al., “AhG 9: APS Cleanup,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 8 pages. cited by applicant

JVET-R0433, Naser, K., et al. “AHG 9: Combination of JVET-R0177/R0301 and JVET-R0074/R0232 on APS Signaling and Semantics Cleanup,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 5 pages. cited by applicant

JVET-P0368-v2, Pettersson, M., et al., “AHG17: On selectively signal slice header parameters in PPS ” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 16th Meeting: Geneva, CH, Oct. 1-11, 2019, 9 pages. cited by applicant

JVET-Q0281, Choi, B., et al., “AHG12: Independently coded regions output window SEI message,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 4 pages. cited by applicant

JVET-R0129-v2, Chen, L., et al., “AHG9/AHG12: On CTU row based slice chunks of a slice within a tile,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 9 pages. cited by applicant

JVET-R0162-V2, Chen, J., et al., “AHG9: PPS and SH syntax cleanup,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 7 pages. cited by applicant

JVET-S0050-v3, Deng, Z., et al., “AHG9: On general constraints information,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 19th Meeting: by teleconference, Jun. 22-Jul. 1, 2020, 9 pages. cited by applicant

JVET-N0073-v1, Chen, L., et al., “AHG17: [SYS-WC] Signalling subpicture coded video sequence,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 14th Meeting: Geneva, Switzerland, Mar. 19-27, 2019, 7 pages. cited by applicant

JVET-P0115-v2, Wang, Y.K et al., “AHG8: Scalability—general and output layer sets,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 16th Meeting: Geneva, CH, Oct. 1-11, 2019, 6 pages. cited by applicant

JVET-Q0117-v1, Wang, Y.K., et al., "AHG9: Cleanups on parameter sets," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 9 pages. cited by applicant

JVET-R0068-V1, Wang, Y.K., et al., "AHG8/AHG9/AHG12: Miscellaneous HLS topics," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 10 pages. cited by applicant

JVET-Q0400-v2, Suehring, K., et al., "AHG9: On extra picture header bits in WC," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 4 pages. cited by applicant

JVET-R0286, Chang, Y.-J., et al., "AhG9: On general constraint information syntax," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 5 pages. cited by applicant

JVET-R0070-v1, Wang, Y.K., et al., "AHG9: On repetition and update of non-VCL data units," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 4 pages. cited by applicant

JVET-P2001-vE, Bross, B., et al., "Versatile Video Coding (Draft 7)," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 16th Meeting: Geneva, CH, Oct. 1-11, 2019, 491 pages. cited by applicant

JVET-02001-vE, Bross, B., et al., "Versatile Video Coding (Draft 6)," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 15th Meeting: Gothenburg, SE, Jul. 3-12, 2019, 455 pages. cited by applicant

JVET-N1001-V10, Bross, B., et al., "Versatile Video Coding (Draft 5)," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 14th Meeting: Geneva, CH, Mar. 19-27, 2019, 407 pages. cited by applicant

JVET-R2001-vA, Bross, B., et al. "Versatile Video Coding (Draft 9)", Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 524 pages. cited by applicant

JVET-Q2001-vD, Bross, B., et al. "Versatile Video Coding (Draft 8)," Joint Video Experts (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29 WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 511 pages. cited by applicant

JVET-P0239-v1, Wan, W., et al., "AHG17: Picture Header," Joint Video Experts (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29 WG 11 16th Meeting: Geneva, CH, Oct. 1-11, 2019, 8 pages. cited by applicant

JVET-S0070-v1, Chen, L., et al., "AHG9: On flag ph_gdr_pr_irap_pic_flag," Joint Video Experts (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29 WG 11 19th Meeting: by teleconference, Jun. 22-Jul. 1, 2020, 4 pages. cited by applicant

Document: JVET-R0060-v1, Wang, Y.K., et al., "AHG9/AHG12: On CLVSs with one slice per picture," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 4 pages. cited by applicant

Document: JVET-Q2001-vC, Bross, B., et al., "Versatile Video Coding (Draft 8)," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 17th Meeting: Brussels, BE, Jan. 7-17, 2020, 508 pages. cited by applicant

Document: JVET-R0118-v2, Choi, B., et al., "AHG9/AHG12: On signaling of subpicture partitioning in SPS," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 3 pages. cited by applicant

Document: JVET-R0227-v1, Sjoberg, R., et al., "AHG9: General constraint information semantics constraints and a flag for PH in SH," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 2 pages. cited by applicant

Document: JVET-R0108-v1, Deshpande, S., et al., "AHG9: Decoding Capability Information and PTL Signalling," Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 4 pages. cited by applicant

Document: JVET-R0343-v1, Hendry, "AHG9: A summary of proposals on parameter sets cleanups," Joint

Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 12 pages. cited by applicant

Document: JVET-R0180, Naser, K., “AhG 9: On ALF, LMCS and Scaling List Parameters Signaling,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 4 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/078188, English Translation of International Search Report dated May 26, 2021, 9 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/078182, English Translation of International Search Report dated May 17, 2021, 12 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/078190, English Translation of International Search Report dated Apr. 25, 2021, 9 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/086868, English Translation of International Search Report dated Jul. 9, 2021, 9 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/086869, English Translation of International Search Report dated Jul. 9, 2021, 12 pages. cited by applicant

Foreign Communication From a Related Counterpart Application, International Application No. PCT/CN2021/086873, English Translation of International Search Report dated Jun. 30, 2021, 12 pages. cited by applicant

Benjamin Bross, Jianle Chen, Shan Liu, and Ye-Kui Wang “Versatile Video Coding (Draft 8),” Joint Video Experts Team (JVET) of ITU-T SG 16 WP3 and ISO/IEC JTC 1/SC 29/WG 11 JVET-Q2001 (version 13) 17th Meeting: Brussels, BEFeb. 9, 2020, pp. 35-36,38-45,54-56,88. cited by applicant

Decision to Grant a Patent for Japanese Application No. 2023-182911, mailed on Oct. 29, 2024, 5 pages. cited by applicant

Decision to Grant a Patent for Japanese Application No. 2023-190717, mailed on Nov. 5, 2024, 5 pages. cited by applicant

Non-Final Office Action for U.S. Appl. No. 17/994,864, mailed Nov. 6, 2024, 20 Pages. cited by applicant

Notice of Reasons for Refusal for Japanese Application No. 2023-189121, mailed Nov. 12, 2024, 8 pages. cited by applicant

Request for the Submission of an Opinion for Korean Application No. 10-2022-7044953, mailed Nov. 14, 2024, 9 pages. cited by applicant

Bross B., et al., “Versatile Video Coding (Draft 7),” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 16th Meeting: Geneva, CH, Oct. 1-11, 2019, Document: JVET-P2001-vB, 491 Pages. cited by applicant

Bross B., et al., “Versatile Video Coding (Draft 9),” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/ IEC JTC 1/SC 29/WG 11, 18th Meeting: by teleconference, Apr. 15-24, 2020, Document: JVET-R2001-vA, JVET-S0152-v5_SpecText, 531 Pages. cited by applicant

Wang Y., et al., “AHG9: A few more general constraints flags,” Joint Video experts Team JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11, 17th Meeting: Brussels, BE, Jan. 7-17, 2020, Document: JVET-Q0114-v1, 3 pages. cited by applicant

Document: JVET-R0191-r1, Hendry, et al., “AHG9: On miscellaneous updates for HLS signalling,” Joint Video Experts Team (JVET) of ITU-T SG 16 WP 3 and ISO/IEC JTC 1/SC 29/WG 11 18th Meeting: by teleconference, Apr. 15-24, 2020, 5 pages. cited by applicant

European Office Action from European Patent Application No. 21760362.0 dated Jan. 31, 2025, 5 pages. cited by applicant

Non-Final Office Action from U.S. Appl. No. 17/994,864 dated Mar. 3, 2025, 42 pages. cited by applicant

Chinese Notice of Allowance from Chinese Patent Application No. 202180017646.9 dated Apr. 11, 2025, 12 pages. cited by applicant

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. application Ser. No. 17/992,270, filed on Nov. 22, 2022, which is a continuation of International Patent Application No. PCT/CN2021/095386, filed on May 24, 2021, which claims the priority to and benefits of International Patent Application No. PCT/CN2020/091740, filed on May 22, 2020. All the aforementioned patent applications are hereby incorporated by reference in their entireties.

TECHNICAL FIELD

(1) The present disclosure relates to image and video coding and decoding.

BACKGROUND

(2) Digital video accounts for the largest bandwidth use on the internet and other digital communication networks. As the number of connected user devices capable of receiving and displaying video increases, it is expected that the bandwidth demand for digital video usage will continue to grow.

SUMMARY

(3) The present disclosure discloses embodiments that can be used by video encoders and decoders for processing a coded representation of video using control information useful for decoding of the coded representation.

(4) In one example aspect, a video processing method is disclosed. The method includes performing a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies that a syntax element is included in a profile, tier, level information syntax structure to indicate whether one or more general constraint information syntax elements are included in a general constraint information syntax structure and/or whether the general constraint information syntax structure is included in the profile, tier, level information syntax structure.

(5) In another example aspect, another video processing method is disclosed. The method includes performing a conversion between a video and a bitstream of the video according to a rule, wherein a syntax structure includes information of one or more video coding layers that are included in the bitstream and correspond to one or more output layer sets, and wherein the rule specifies that a starting position of a syntax element in the syntax structure that specifies a level information to which the one or more output layer sets conform is constrained to align to a byte boundary.

(6) In another example aspect, another video processing method is disclosed. The method includes performing a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies that a syntax structure indicates constraint information about the bitstream, and wherein the rule specifies that the syntax structure is allowed to include a syntax element without aligning to a byte boundary.

(7) In another example aspect, another video processing method is disclosed. The method includes performing a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies where and how reserved bits are included in a syntax structure that indicates one or more coding constraints applicable to the conversion.

(8) In another example aspect, another video processing method is disclosed. The method includes determining, for a conversion between a video comprising one or more pictures comprising one or more slices and a bitstream of the video, that only I slices are enabled for the conversion according to a rule; and performing the conversion according to the determining, wherein the rule specifies that, responsive to only I slices being enabled, the bitstream conforms to one or more additional constraints.

(9) In another example aspect, another video processing method is disclosed. The method includes performing a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies that one or more syntax elements in a sequence parameter set, a picture parameter set, a picture header, or a sequence header are constrained according to a general constraint information syntax element

that indicates a constraint applicable to the conversion.

(10) In another example aspect, another video processing method is disclosed. The method includes performing a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies that whether or how a first syntax element in a syntax structure that indicates one or more constraints applicable to the conversion is indicated is dependent on whether or how a second syntax element is indicated in the syntax structure.

(11) In another example aspect, another video processing method is disclosed. The method includes performing a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies whether or how a syntax element indicative of general constraints on the conversion is included in the bitstream depends on a profile and/or a level used for the conversion.

(12) In yet another example aspect, a video encoder apparatus is disclosed. The video encoder comprises a processor configured to implement above-described methods.

(13) In yet another example aspect, a video decoder apparatus is disclosed. The video decoder comprises a processor configured to implement above-described methods.

(14) In yet another example aspect, a computer readable medium having code stored thereon is disclosed. The code embodies one of the methods described herein in the form of processor-executable code.

(15) These, and other, features are described throughout the present disclosure.

Description

BRIEF DESCRIPTION OF DRAWINGS

(1) FIG. 1 is a block diagram of an example video processing system.

(2) FIG. 2 is a block diagram of a video processing apparatus.

(3) FIG. 3 is a flowchart for an example method of video processing.

(4) FIG. 4 is a block diagram that illustrates a video coding system in accordance with some embodiments of the present disclosure.

(5) FIG. 5 is a block diagram that illustrates an encoder in accordance with some embodiments of the present disclosure.

(6) FIG. 6 is a block diagram that illustrates a decoder in accordance with some embodiments of the present disclosure.

(7) FIG. 7 is a flowchart for an example method of video processing based on some embodiments of the present disclosure.

(8) FIGS. 8A and 8B are flowcharts for example methods of video processing based on some embodiments of the present disclosure.

(9) FIGS. 9A to 9E are flowcharts for example methods of video processing based on some embodiments of the present disclosure.

DETAILED DESCRIPTION

(10) Section headings are used in the present disclosure for ease of understanding and do not limit the applicability of embodiments disclosed in each section only to that section. Furthermore, H.266 terminology is used in some description only for ease of understanding and not for limiting scope of the disclosed embodiments. As such, the embodiments described herein are applicable to other video codec protocols and designs also.

1. Introduction

(11) This disclosure is related to video coding technologies. Specifically, it is about the design of constraint flags related syntax in video coding. The ideas may be applied individually or in various combination, to any video coding standard or non-standard video codec that supports multi-layer video coding, e.g., the being-developed Versatile Video Coding (VVC).

2. Abbreviations

(12) ALF Adaptive Loop Filter APS Adaptation Parameter Set AU Access Unit AUD Access Unit
Delimiter AVC Advanced Video Coding CCALF Cross-Component ALF CLVS Coded Layer Video
Sequence CPB Coded Picture Buffer CRA Clean Random Access CTB Coding Tree Block CTU Coding
Tree Unit CU Coding Unit CVS Coded Video Sequence DCI Decoding Capability Information DPB
Decoded Picture Buffer DPS Decoding Parameter Set EOB End Of Bitstream EOS End Of Sequence

GDR Gradual Decoding Refresh HEVC High Efficiency Video Coding HRD Hypothetical Reference Decoder IDR Instantaneous Decoding Refresh ILRP Inter-Layer Reference Picture IRAP Intra Random Access Points JEM Joint Exploration Model LMCS Luma Mapping with Chroma Scaling LSB(s) Least-Significant Bit(s) LTRP Long-Term Reference Picture MCTS Motion-Constrained Tile Sets MSB(s) Most-Significant Bit(s) NAL Network Abstraction Layer OLS Output Layer Set PH Picture Header POC Picture Order Count PPS Picture Parameter Set PTL Profile, Tier and Level PU Picture Unit QP Quantization Parameter RBSP Raw Byte Sequence Payload RPL Reference Picture List RPR Reference Picture Resampling SAO Sample Adaptive Offset SBT Sub-block Transform SEI Supplemental Enhancement Information SH Slice Header SPS Sequence Parameter Set STRP Short-Term Reference Picture SVC Scalable Video Coding VCL Video Coding Layer VPS Video Parameter Set VTM VVC Test Model VUI Video Usability Information VVC Versatile Video Coding

3. Background

(13) Video coding standards have evolved primarily through the development of the well-known International Telecommunication Union (ITU) Telecommunication Standardization Sector (ITU-T) and International Organization for Standardization (ISO)/International Electrotechnical Commission (IEC) standards. The ITU-T produced H.261 and H.263, ISO/IEC produced Moving Picture Experts Group (MPEG)-1 and MPEG-4 Visual, and the two organizations jointly produced the H.262/MPEG-2 Video and H.264/MPEG-4 Advanced Video Coding (AVC) and H.265/HEVC standards. Since H.262, the video coding standards are based on the hybrid video coding structure wherein temporal prediction plus transform coding are utilized. To explore the future video coding technologies beyond HEVC, the Joint Video Exploration Team (JVET) was founded by Video Coding Experts Group (VCEG) and MPEG jointly in 2015. Since then, many new methods have been adopted by JVET and put into the reference software named Joint Exploration Model (JEM). The JVET meeting is concurrently held once every quarter, and the new coding standard is targeting a 50% bitrate reduction as compared to HEVC. The new video coding standard was officially named as Versatile Video Coding (VVC) in the April 2018 JVET meeting, and the first version of VVC test model (VTM) was released at that time. As there are continuous effort contributing to VVC standardization, new coding techniques are being adopted to the VVC standard in every JVET meeting. The VVC working draft and test model VTM are then updated after every meeting. The VVC project is now aiming for technical completion (FDIS) at the July 2020 meeting.

(14) 3.1. General Profile, Tier, Level Syntax and Semantics

(15) In the latest VVC draft text, the general profile, tier, level syntax and semantics are as follows:

(16) TABLE-US-00001 Descriptor `profile_tier_level( profileTierPresentFlag, maxNumSubLayersMinus1 )` {
 if(profileTierPresentFlag) {
 general_profile_idc u(7)
 general_tier_flag u(1)
 general_constraint_info()
 }
 general_level_idc u(8)
 if(profileTierPresentFlag) {
 num_sub_profiles u(8)
 for(i = 0; i < num_sub_profiles; i++)
 general_sub_profile_idc[i] u(32)
 for(i = 0; i < max_NumSubLayersMinus1; i++)
 sublayer_level_present_flag[i] u(1)
 while(!byte_aligned())
 ptl_alignment_zero_bit f(1)
 for(i = 0; i < maxNumSubLayersMinus1; i++)
 if(sublayer_level_present_flag[i])
 sublayer_level_idc[i] u(8)
 }
}

A `profile_tier_level( )` syntax structure provides level information and, optionally, profile, tier, sub-profile, and general constraints information.

When the `profile_tier_level( )` syntax structure is included in a VPS, the `OlsInScope` is one or more OLSs specified by the VPS. When the `profile_tier_level( )` syntax structure is included in an SPS, the `OlsInScope` is the OLS that includes only the layer that is the lowest layer among the layers that refer to the SPS, and this lowest layer is an independent layer.

`general_profile_idc` indicates a profile to which `OlsInScope` conforms as specified in Annex A. Bitstreams shall not contain values of `general_profile_idc` other than those specified in Annex A. Other values of `general_profile_idc` are reserved for future use by ITU-T|ISO/IEC.

`general_tier_flag` specifies the tier context for the interpretation of `general_level_idc` as specified in Annex A.

`general_level_idc` indicates a level to which `OlsInScope` conforms as specified in Annex A. Bitstreams shall not contain values of `general_level_idc` other than those specified in Annex A. Other values of `general_level_idc` are reserved for future use by ITU-T|ISO/IEC. NOTE 1—A greater value of `general_level_idc` indicates a higher level. The maximum level signalled in the DCI NAL unit for

OlsInScope may be higher than 0 but cannot be lower than the level signalled in the SPS for a CLVS contained within OlsInScope. NOTE 2—When OlsInScope conforms to multiple profiles, general_profile_idc should indicate the profile that provides the preferred decoded result or the preferred bitstream identification, as determined by the encoder (in a manner not specified in this Specification). NOTE 3—When the CVSSs of OlsInScope conform to different profiles, multiple profile_tier_level() syntax structures may be included in the DCI NAL unit such that for each CVS of the OlsInScope there is at least one set of indicated profile, tier, and level for a decoder that is capable of decoding the CVS. num_sub_profiles specifies the number of the general_sub_profile_idc[i] syntax elements. general_sub_profile_idc[i] indicates the i-th interoperability metadata registered as specified by Rec. ITU-T T.35, the contents of which are not specified in this Specification. sublayer_level_present_flag[i] equal to 1 specifies that level information is present in the profile_tier_level() syntax structure for the sublayer representation with TemporalId equal to i. sublayer_level_present_flag[i] equal to 0 specifies that level information is not present in the profile_tier_level() syntax structure for the sublayer representation with TemporalId equal to i. ptl_alignment_zero_bits shall be equal to 0.

The semantics of the syntax element sublayer_level_idc[i] is, apart from the specification of the inference of not present values, the same as the syntax element general_level_idc, but apply to the sublayer representation with TemporalId equal to i.

When not present, the value of sublayer_level_idc[i] is inferred as follows:

sublayer_level_idc[maxNumSubLayersMinus1] is inferred to be equal to general_level_idc of the same profile_tier_level() structure, For i from maxNumSubLayersMinus1-1 to 0 (in decreasing order of values of i), inclusive, sublayer_level_idc[i] is inferred to be equal to sublayer_level_idc[i+1].

3.2. General Constraint Information Syntax and Semantics

(17) In the latest VVC draft text, the general constraint information syntax and semantics are as follows:

(18) TABLE-US-00002 Descriptor general_constraint_info() {
general_progressive_source_flag u(1)
general_interlaced_source_flag u(1) **general**_non_packed_constraint_flag u(1)
general_frame_only_constraint_flag u(1) **general**_non_projected_constraint_flag u(1)
intra_only_constraint_flag u(1) **max**_bitdepth_constraint_idc u(4)
max_chroma_format_constraint_idc u(2) **no**_res_change_in_clvs_constraint_flag u(1)
one_tile_per_pic_constraint_flag u(1) **one**_slice_per_pic_constraint_flag u(1)
one_subpic_per_pic_constraint_flag u(1) **no**_qtbtt_dual_tree_intra_constraint_flag u(1)
no_partition_constraints_override_constraint_flag u(1) **no**_sao_constraint_flag u(1)
no_alf_constraint_flag u(1) **no**_ccalf_constraint_flag u(1) **no**_joint_cbr_constraint_flag u(1)
no_ref_wraparound_constraint_flag u(1) **no**_temporal_mvp_constraint_flag u(1)
no_sbtmvp_constraint_flag u(1) **no**_amvr_constraint_flag u(1) **no**_bdof_constraint_flag u(1)
no_dmvr_constraint_flag u(1) **no**_cclm_constraint_flag u(1) **no**_mts_constraint_flag u(1)
no_sbt_constraint_flag u(1) **no**_affine_motion_constraint_flag u(1) **no**_bcw_constraint_flag u(1)
no_ibc_constraint_flag u(1) **no**_ciip_constraint_flag u(1) **no**_fpel_mmvd_constraint_flag u(1)
no_gpm_constraint_flag u(1) **no**_ladf_constraint_flag u(1) **no**_transform_skip_constraint_flag u(1)
no_bdpcm_constraint_flag u(1) **no**_qp_delta_constraint_flag u(1) **no**_dep_quant_constraint_flag u(1)
no_sign_data_hiding_constraint_flag u(1) **no**_mixed_nalu_types_in_pic_constraint_flag u(1)
no_trail_constraint_flag u(1) **no**_stsa_constraint_flag u(1) **no**_rasl_constraint_flag u(1)
no_radl_constraint_flag u(1) **no**_idr_constraint_flag u(1) **no**_cra_constraint_flag u(1)
no_gdr_constraint_flag u(1) **no**_aps_constraint_flag u(1) while(!byte_aligned())
gci_alignment_zero_bit f(1) **num**_reserved_constraint_bytes u(8) for(i = 0; i <
num_reserved_constraint_bytes; i++) **gci**_reserved_constraint_byte[i] u(8) }

general_progressive_source_flag and general_interlaced_source_flag are interpreted as follows: If general_progressive_source_flag is equal to 1 and general_interlaced_source_flag is equal to 0, the source scan type of the pictures in OlsInScope should be interpreted as progressive only. Otherwise, if general_progressive_source_flag is equal to 0 and general_interlaced_source_flag is equal to 1, the source scan type of the pictures in OlsInScope should be interpreted as interlaced only. Otherwise, if general_progressive_source_flag is equal to 0 and general_interlaced_source_flag is equal to 0, the source scan type of the pictures in OlsInScope should be interpreted as unknown or unspecified. Otherwise

(general_progressive_source_flag is equal to 1 and general_interlaced_source_flag is equal to 1), the source scan type of each picture in OlsInScope is indicated at the picture level using the syntax element source_scan_type in a frame-field information SEI message. It is a requirement of bitstream conformance that when general_progressive_source_flag is equal to 1 and general_interlaced_source_flag is equal to 1, a frame-field information SEI message shall be present in each AU. NOTE 1—Decoders may ignore the values of general_progressive_source_flag and general_interlaced_source_flag. Moreover, the actual source scan type of the pictures is outside the scope of this Specification and the method by which the encoder selects the values of general_progressive_source_flag and general_interlaced_source_flag is unspecified.

general_non_packed_constraint_flag equal to 1 specifies that there shall not be any frame packing arrangement SEI messages present in the bitstream of the OlsInScope.

general_non_packed_constraint_flag equal to 0 does not impose such a constraint. NOTE 2—Decoders may ignore the value of general_non_packed_constraint_flag, as there are no decoding process requirements associated with the presence or interpretation of frame packing arrangement SEI messages.

general_frame_only_constraint_flag equal to 1 specifies that OlsInScope conveys pictures that represent frames. general_frame_only_constraint_flag equal to 0 specifies that OlsInScope conveys pictures that may or may not represent frames. NOTE 3—Decoders may ignore the value of

general_frame_only_constraint_flag, as there are no decoding process requirements associated with it.

general_non_projected_constraint_flag equal to 1 specifies that there shall not be any equirectangular projection SEI messages or generalized cubemap projection SEI messages present in the bitstream of the OlsInScope. general_non_projected_constraint_flag equal to 0 does not impose such a constraint. NOTE 4—Decoders may ignore the value of general_non_projected_constraint_flag, as there are no decoding process requirements associated with the presence or interpretation of equirectangular projection SEI messages and generalized cubemap projection SEI messages.

intra_only_constraint_flag equal to 1 specifies that slice_type shall be equal to 1.

intra_only_constraint_flag equal to 0 does not impose such a constraint.

max_bitdepth_constraint_idc specifies that bit_depth_minus8 shall be in the range of 0 to max_bitdepth_constraint_idc, inclusive.

max_chroma_format_constraint_idc specifies that chroma_format_idc shall be in the range of 0 to max_chroma_format_constraint_idc, inclusive.

no_res_change_in_clvs_constraint_flag equal to 1 specifies that res_change_in_clvs_allowed_flag shall be equal to 0. no_res_change_in_clvs_constraint_flag equal to 0 does not impose such a constraint.

one_tile_per_pic_constraint_flag equal to 1 specifies that each picture shall contain only one tile.

one_tile_per_pic_constraint_flag equal to 0 does not impose such a constraint.

one_slice_per_pic_constraint_flag equal to 1 specifies that each picture shall contain only one slice.

one_slice_per_pic_constraint_flag equal to 0 does not impose such a constraint.

one_subpic_per_pic_constraint_flag equal to 1 specifies that each picture shall contain only one subpicture.

one_subpic_per_pic_constraint_flag equal to 0 does not impose such a constraint. When

one_slice_per_pic_constraint_flag is equal to 1, the value of one_subpic_per_pic_constraint_flag shall be equal to 1.

no_qtbt_dual_tree_intra_constraint_flag equal to 1 specifies that qtbt_dual_tree_intra_flag shall be equal to 0. no_qtba_dual_tree_intra_constraint_flag equal to 0 does not impose such a constraint.

no_partition_constraints_override_constraint_flag equal to 1 specifies that partition_constraints_override_enabled_flag shall be equal to 0.

no_partition_constraints_override_constraint_flag equal to 0 does not impose such a constraint.

no_sao_constraint_flag equal to 1 specifies that sps_sao_enabled_flag shall be equal to 0.

no_sao_constraint_flag equal to 0 does not impose such a constraint.

no_alf_constraint_flag equal to 1 specifies that sps_alf_enabled_flag shall be equal to 0.

no_alf_constraint_flag equal to 0 does not impose such a constraint.

no_ccalf_constraint_flag equal to 1 specifies that sps_ccalf_enabled_flag shall be equal to 0.

no_ccalf_constraint_flag equal to 0 does not impose such a constraint.

no_joint_cbr_constraint_flag equal to 1 specifies that sps_joint_cbr_enabled_flag shall be equal to 0.

no_joint_cbr_constraint_flag equal to 0 does not impose such a constraint.

no_ref_wraparound_constraint_flag equal to 1 specifies that sps_ref_wraparound_enabled_flag shall be equal to 0. no_ref_wraparound_constraint_flag equal to 0 does not impose such a constraint.

no_temporal_mvp_constraint_flag equal to 1 specifies that sps_temporal_mvp_enabled_flag shall be equal to 0. no_temporal_mvp_constraint_flag equal to 0 does not impose such a constraint.

no_sbtmvp_constraint_flag equal to 1 specifies that sps_sbtmvp_enabled_flag shall be equal to 0. no_sbtmvp_constraint_flag equal to 0 does not impose such a constraint.

no_amvr_constraint_flag equal to 1 specifies that sps_amvr_enabled_flag shall be equal to 0. no_amvr_constraint_flag equal to 0 does not impose such a constraint.

no_bdof_constraint_flag equal to 1 specifies that sps_bdof_enabled_flag shall be equal to 0. no_bdof_constraint_flag equal to 0 does not impose such a constraint.

no_dmvr_constraint_flag equal to 1 specifies that sps_dmvr_enabled_flag shall be equal to 0. no_dmvr_constraint_flag equal to 0 does not impose such a constraint.

no_cclm_constraint_flag equal to 1 specifies that sps_cclm_enabled_flag shall be equal to 0. no_cclm_constraint_flag equal to 0 does not impose such a constraint.

no_mts_constraint_flag equal to 1 specifies that sps_mts_enabled_flag shall be equal to 0. no_mts_constraint_flag equal to 0 does not impose such a constraint.

no_sbt_constraint_flag equal to 1 specifies that sps_sbt_enabled_flag shall be equal to 0. no_sbt_constraint_flag equal to 0 does not impose such a constraint.

no_affine_motion_constraint_flag equal to 1 specifies that sps_affine_enabled_flag shall be equal to 0. no_affine_motion_constraint_flag equal to 0 does not impose such a constraint.

no_bcw_constraint_flag equal to 1 specifies that sps_bcw_enabled_flag shall be equal to 0. no_bcw_constraint_flag equal to 0 does not impose such a constraint.

no_ibc_constraint_flag equal to 1 specifies that sps_ibc_enabled_flag shall be equal to 0. no_ibc_constraint_flag equal to 0 does not impose such a constraint.

no_ciip_constraint_flag equal to 1 specifies that sps_ciip_enabled_flag shall be equal to 0. no_cipp_constraint_flag equal to 0 does not impose such a constraint.

no_fpel_mmvd_constraint_flag equal to 1 specifies that sps_fpel_mmvd_enabled_flag shall be equal to 0. no_fpel_mmvd_constraint_flag equal to 0 does not impose such a constraint.

no_gpm_constraint_flag equal to 1 specifies that sps_gpm_enabled_flag shall be equal to 0. no_gpm_constraint_flag equal to 0 does not impose such a constraint.

no_ladf_constraint_flag equal to 1 specifies that sps_ladf_enabled_flag shall be equal to 0. no_ladf_constraint_flag equal to 0 does not impose such a constraint.

no_transform_skip_constraint_flag equal to 1 specifies that sps_transform_skip_enabled_flag shall be equal to 0. no_transform_skip_constraint_flag equal to 0 does not impose such a constraint.

no_bdpcm_constraint_flag equal to 1 specifies that sps_bdpcm_enabled_flag shall be equal to 0. no_bdpcm_constraint_flag equal to 0 does not impose such a constraint.

no_qp_delta_constraint_flag equal to 1 specifies that it is a requirement of bitstream conformance that cu_qp_delta_enabled_flag shall be equal to 0. no_qp_delta_constraint_flag equal to 0 does not impose such a constraint.

no_dep_quant_constraint_flag equal to 1 specifies that it is a requirement of bitstream conformance that sps_dep_quant_enabled_flag shall be equal to 0. no_dep_quant_constraint_flag equal to 0 does not impose such a constraint.

no_sign_data_hiding_constraint_flag equal to 1 specifies that it is a requirement of bitstream conformance that sps_sign_data_hiding_enabled_flag shall be equal to 0. no_sign_data_hiding_constraint_flag equal to 0 does not impose such a constraint.

no_mixed_nalu_types_in_pic_constraint_flag equal to 1 specifies that it is a requirement of bitstream conformance that mixed_nalu_types_in_pic_flag shall be equal to 0. no_mixed_nalu_types_in_pic_constraint_flag equal to 0 does not impose such a constraint.

no_trail_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to TRAIL_NUT present in OlsInScope. no_trail_constraint_flag equal to 0 does not impose such a constraint.

no_stsa_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to STSA_NUT present in OlsInScope. no_stsa_constraint_flag equal to 0 does not impose such a constraint.

no_rasl_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to RASL_NUT present in OlsInScope. no_rasl_constraint_flag equal to 0 does not impose such a constraint. no_radl_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to RADL_NUT present in OlsInScope. no_radl_constraint_flag equal to 0 does not impose such a constraint. no_idr_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to IDR_W_RADL or IDR_N_LP present in OlsInScope. no_idr_constraint_flag equal to 0 does not impose such a constraint.

no_cra_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to CRA_NUT present in OlsInScope. no_cra_constraint_flag equal to 0 does not impose such a constraint. no_gdr_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to GDR_NUT present in OlsInScope. no_gdr_constraint_flag equal to 0 does not impose such a constraint. no_aps_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT present in OlsInScope. no_aps_constraint_flag equal to 0 does not impose such a constraint.

gci_alignment_zero_bits shall be equal to 0.

num_reserved_constraint_bytes specifies the number of the reserved constraint bytes. The value of num_reserved_constraint_bytes shall be 0. Other values of num_reserved_constraint_bytes are reserved for future use by ITU-T|ISO/IEC and shall not be present in bitstreams conforming to this version of this Specification.

gci_reserved_constraint_byte[i] may have any value. Its presence and value do not affect decoder conformance to profiles specified in this version of this Specification. Decoders conforming to this version of this Specification shall ignore the values of all the gci_reserved_constraint_byte[i] syntax elements.

3.3. DCI Syntax and Semantics

(19) In the latest VVC draft text, the DCI syntax and semantics are as follows:

(20) TABLE-US-00003 Descriptor decoding_capability_information_rbsp() {

```
dci_max_sublayers_minus1 u(3)    dci_reserved_zero_bit u(1)    dci_num_ptls_minus1 u(4)    for( i = 0;
i <= dci_num_ptls_minus1; i++ )    profile_tier_level( 1, 0 )    dci_extension_flag u(1)    if(
dci_extension_flag )    while( more_rbsp_data( ) )    dci_extension_data_flag u(1)
rbsp_trailing_bits( ) }
```

A DCI RBSP may be made available to the decoder, through either being present in the bitstream, included in at least the first AU of the bitstream, or provided through external means. NOTE 1—The information contained in the DCI RBSP is not necessary for operation of the decoding process specified in clauses 2 through 9 of this Specification.

When present, all DCI NAL units in a bitstream shall have the same content.

dci_max_sublayers_minus1 plus 1 specifies the maximum number of temporal sublayers that may be present in a layer in each CVS of the bitstream. The value of dci_max_sublayers_minus1 shall be in the range of 0 to 6, inclusive.

dci_reserved_zero_bit shall be equal to 0 in bitstreams conforming to this version of this Specification. The value 1 for dci_reserved_zero_bit is reserved for future use by ITU-T|ISO/IEC.

dci_num_ptls_minus1 plus 1 specifies the number of profile_tier_level() syntax structures in the DCI NAL unit. It is a requirement of bitstream conformance that each OLS in a CVS in the bitstream shall conform to at least one of the profile_tier_level() syntax structures in the DCI NAL unit. NOTE 2—The DCI NAL unit may include PTL information, possibly carried in multiple profile_tier_level() syntax structures, that applies collectively to multiple OLSs, and does not need to include PTL information for each of the OLSs individually.

dci_extension_flag equal to 0 specifies that no dci_extension_data_flag syntax elements are present in the DCI RBSP syntax structure. dci_extension_flag equal to 1 specifies that there are dci_extension_data_flag syntax elements present in the DCI RBSP syntax structure.

dci_extension_data_flag may have any value. Its presence and value do not affect decoder conformance to profiles specified in Annex A. Decoders conforming to this version of this Specification shall ignore all dci_extension_data_flag syntax elements.

3.4. VPS Syntax and Semantics

In the latest VVC draft text, the VPS syntax and semantics are as follows:

```
(21) TABLE-US-00004 Descriptor video_parameter_set_rbsp( ) {    vps_video_parameter_set_id u(4)
vps_max_layers_minus1 u(6)    vps_max_sublayers_minus1 u(3)    if( vps_max_layers_minus1 > 0 &&
    vps_max_sublayers_minus1 > 0 )    vps_all_layers_same_num_sublayers_flag u(1)    if(
vps_max_layers_minus1 > 0 )    vps_all_independent_layers_flag u(1)    for( i = 0; i <=
vps_max_layers_minus1; i++ ) {    vps_layer_id[ i ] u(6)    if( i > 0 &&
!vps_all_independent_layers_flag ) {    vps_independent_layer_flag[ i ] u(1)    if(
!vps_independent_layer_flag[ i ] ) {    for( j = 0; j < i; j++ )
vps_direct_ref_layer_flag[ i ][ j ] u(1)    max_tid_ref_present_flag[ i ] u(1)    if(
max_tid_ref_present_flag[ i ] )    max_tid_il_ref_pics_plus1[ i ] u(3)    }    }    }    if(
vps_max_layers_minus1 > 0 ) {    if( vps_all_independent_layers_flag )
each_layer_is_an_ols_flag u(1)    if( !each_layer_is_an_ols_flag ) {    if(
!vps_all_independent_layers_flag )    ols_mode_idc u(2)    if( ols_mode_idc == 2 ) {
num_output_layer_sets_minus1 u(8)    for( i = 1; i <=
num_output_layer_sets_minus1; i++ )    for( j = 0; j <= vps_max_layers_minus1; j++ )
ols_output_layer_flag[ i ][ j ] u(1)    }    }    }    vps_num_ptls_minus1 u(8)
for( i = 0; i <= vps_num_ptls_minus1; i++ ) {    if( i > 0 )    pt_present_flag[ i ] u(1)    if(
vps_max_sublayers_minus1 > 0 && !vps_all_layers_same_num_sublayers_flag )
ptl_max_temporal_id[ i ] u(3)    }    while( !byte_aligned( ) )    vps_ptl_alignment_zero_bit /* equal
to 0 */ f(1)    for( i = 0; i <= vps_num_ptls_minus1; i++ )    profile_tier_level( pt_present_flag[ i ],
ptl_max_temporal_id[ i ] )    for( i = 0; i < TotalNumOls; i++ )    if( vps_num_ptls_minus1 > 0 )
ols_ptl_idx[ i ] u(8)    if( !vps_all_independent_layers_flag )    vps_num_dpb_params ue(v)
if( vps_num_dpb_params > 0 && vps_max_sublayers_minus1 > 0 )
vps_sublayer_dpb_params_present_flag u(1)    for( i = 0; i < vps_num_dpb_params; i++ ) {    if(
vps_max_sublayers_minus1 > 0 && !vps_all_layers_same_num_sublayers_flag )
dpb_max_temporal_id[ i ] u(3)    dpb_parameters( dpb_max_temporal_id[ i ],
vps_sublayer_dpb_params_present_flag )    }    for( i = 0; i < TotalNumOls; i++ ) {    if(
NumLayersInOls[ i ] > 1 ) {    ols_dpb_pic_width[ i ] ue(v)    ols_dpb_pic_height[ i ] ue(v)
if( vps_num_dpb_params > 1 )    ols_dpb_params_idx[ i ] ue(v)    }    }    if(
!each_layer_is_an_ols_flag )    vps_general_hrd_params_present_flag u(1)    if(
vps_general_hrd_params_present_flag ) {    general_hrd_parameters( )    if(
vps_max_sublayers_minus1 > 0 )    vps_sublayer_cpb_params_present_flag u(1)
num_ols_hrd_params_minus1 ue(v)    for( i = 0; i <= num_ols_hrd_params_minus1; i++ ) {    if(
vps_max_sublayers_minus1 > 0 && !vps_all_layers_same_num_sublayers_flag )
hrd_max_tid[ i ] u(3)    firstSubLayer = vps_sublayer_cpb_params_present_flag ? 0 :
hrd_max_tid[ i ]    ols_hrd_parameters( firstSubLayer, hrd_max_tid[ i ] )    }    if(
num_ols_hrd_params_minus1 + 1 != TotalNumOls &&
num_ols_hrd_params_minus1 > 0 )    for( i = 1; i < TotalNumOls; i++ )    if(
NumLayersInOls[ i ] > 1 )    ols_hrd_idx[ i ] ue(v)    }    vps_extension_flag u(1)    if(
vps_extension_flag )    while( more_rbsp_data( ) )    vps_extension_data_flag u(1)
rbsp_trailing_bits( ) }
```

A VPS RBSP shall be available to the decoding process prior to it being referenced, included in at least one AU with TemporalId equal to 0 or provided through external means.

All VPS NAL units with a particular value of vps_video_parameter_set_id in a CVS shall have the same content.

vps_video_parameter_set_id provides an identifier for the VPS for reference by other syntax elements.

The value of vps_video_parameter_set_id shall be greater than 0.

vps_max_layers_minus1 plus 1 specifies the maximum allowed number of layers in each CVS referring to the VPS.

vps_max_sublayers_minus1 plus 1 specifies the maximum number of temporal sublayers that may be present in a layer in each CVS referring to the VPS. The value of vps_max_sublayers_minus1 shall be in the range of 0 to 6, inclusive.

vps_all_layers_same_num_sublayers_flag equal to 1 specifies that the number of temporal sublayers is the

same for all the layers in each CVS referring to the VPS. `vps_all_layers_same_num_sublayers_flag` equal to 0 specifies that the layers in each CVS referring to the VPS may or may not have the same number of temporal sublayers. When not present, the value of `vps_all_layers_same_num_sublayers_flag` is inferred to be equal to 1.

`vps_all_independent_layers_flag` equal to 1 specifies that all layers in the CVS are independently coded without using inter-layer prediction. `vps_all_independent_layers_flag` equal to 0 specifies that one or more of the layers in the CVS may use inter-layer prediction. When not present, the value of `vps_all_independent_layers_flag` is inferred to be equal to 1.

`vps_layer_id[i]` specifies the `nuh_layer_id` value of the *i*-th layer. For any two non-negative integer values of *m* and *n*, when *m* is less than *n*, the value of `vps_layer_id[m]` shall be less than `vps_layer_id[n]`.

`vps_independent_layer_flag[i]` equal to 1 specifies that the layer with index *i* does not use inter-layer prediction. `vps_independent_layer_flag[i]` equal to 0 specifies that the layer with index *i* may use inter-layer prediction and the syntax elements `vps_direct_ref_layer_flag[i][j]` for *j* in the range of 0 to *i*−1, inclusive, are present in VPS. When not present, the value of `vps_independent_layer_flag[i]` is inferred to be equal to 1.

`vps_direct_ref_layer_flag[i][j]` equal to 0 specifies that the layer with index *j* is not a direct reference layer for the layer with index *i*. `vps_direct_ref_layer_flag[i][j]` equal to 1 specifies that the layer with index *j* is a direct reference layer for the layer with index *i*. When `vps_direct_ref_layer_flag[i][j]` is not present for *i* and *j* in the range of 0 to `vps_max_layers_minus1`, inclusive, it is inferred to be equal to 0. When `vps_independent_layer_flag[i]` is equal to 0, there shall be at least one value of *j* in the range of 0 to *i*−1, inclusive, such that the value of `vps_direct_ref_layer_flag[i][j]` is equal to 1.

The variables `NumDirectRefLayers[i]`, `DirectRefLayerIdx[i][d]`, `NumRefLayers[i]`, `RefLayerIdx[i][r]`, and `LayerUsedAsRefLayerFlag[j]` are derived as follows:

```
(22) TABLE-US-00005 for( i = 0; i <= vps_max_layers_minus1; i++ ) {   for( j = 0; j <=
vps_max_layers_minus1; j++ ) {       dependencyFlag[ i ][ j ] = vps_direct_ref_layer_flag[ i ][ j ]
for( k = 0; k < i; k++ )           if( vps_direct_ref_layer_flag[ i ][ k ] && dependencyFlag[ k ][ j ] )
            dependencyFlag[ i ][ j ] = 1   }   LayerUsedAsRefLayerFlag[ i ] = 0 } for( i = 0; i <=
vps_max_layers_minus1; i++ ) {   for( j = 0, d = 0, r = 0; j <= vps_max_layers_minus1; j++ ) { (37)
            if( vps_direct_ref_layer_flag[ i ][ j ] ) {               DirectRefLayerIdx[ i ][ d++ ] = j
LayerUsedAsRefLayerFlag[ j ] = 1           }           if( dependencyFlag[ i ][ j ] )           RefLayerIdx[ i ][ r++ ]
= j   }   NumDirectRefLayers[ i ] = d   NumRefLayers[ i ] = r }
```

The variable `GeneralLayerIdx[i]`, specifying the layer index of the layer with `nuh_layer_id` equal to `vps_layer_id[i]`, is derived as follows:

```
for( i=0; i<=vps_max_layers_minus1; i++)GeneralLayerIdx[vps_layer_id[i]]=i   (38)
```

For any two different values of *i* and *j*, both in the range of 0 to `vps_max_layers_minus1`, inclusive, when `dependencyFlag[i][j]` equal to 1, it is a requirement of bitstream conformance that the values of `chroma_format_idc` and `bit_depth_minus8` that apply to the *i*-th layer shall be equal to the values of `chroma_format_idc` and `bit_depth_minus8`, respectively, that apply to the *j*-th layer.

`max_tid_ref_present_flag[i]` equal to 1 specifies that the syntax element `max_tid_il_ref_pics_plus1[i]` is present. `max_tid_ref_present_flag[i]` equal to 0 specifies that the syntax element `max_tid_il_ref_pics_plus1[i]` is not present.

`max_tid_il_ref_pics_plus1[i]` equal to 0 specifies that inter-layer prediction is not used by non-IRAP pictures of the *i*-th layer. `max_tid_il_ref_pics_plus1[i]` greater than 0 specifies that, for decoding pictures of the *i*-th layer, no picture with `TemporalId` greater than `max_tid_il_ref_pics_plus1[i]`−1 is used as ILRP. When not present, the value of `max_tid_il_ref_pics_plus1[i]` is inferred to be equal to 7.

`each_layer_is_an_ols_flag` equal to 1 specifies that each OLS contains only one layer and each layer itself in a CVS referring to the VPS is an OLS with the single included layer being the only output layer.

`each_layer_is_an_ols_flag` equal to 0 that an OLS may contain more than one layer. If

`vps_max_layers_minus1` is equal to 0, the value of `each_layer_is_an_ols_flag` is inferred to be equal to 1. Otherwise, when `vps_all_independent_layers_flag` is equal to 0, the value of `each_layer_is_an_ols_flag` is inferred to be equal to 0.

`ols_mode_idc` equal to 0 specifies that the total number of OLSs specified by the VPS is equal to `vps_max_layers_minus1`+1, the *i*-th OLS includes the layers with layer indices from 0 to *i*, inclusive, and

for each OLS only the highest layer in the OLS is output.

ols_mode_idc equal to 1 specifies that the total number of OLSs specified by the VPS is equal to vps_max_layers_minus1+1, the i-th OLS includes the layers with layer indices from 0 to i, inclusive, and for each OLS all layers in the OLS are output.

ols_mode_idc equal to 2 specifies that the total number of OLSs specified by the VPS is explicitly signalled and for each OLS the output layers are explicitly signalled and other layers are the layers that are direct or indirect reference layers of the output layers of the OLS.

The value of ols_mode_idc shall be in the range of 0 to 2, inclusive. The value 3 of ols_mode_idc is reserved for future use by ITU-T|ISO/IEC.

When vps_all_independent_layers_flag is equal to 1 and each_layer_is_an_ols_flag is equal to 0, the value of ols_mode_idc is inferred to be equal to 2.

num_output_layer_sets_minus1 plus 1 specifies the total number of OLSs specified by the VPS when ols_mode_idc is equal to 2.

The variable TotalNumOlss, specifying the total number of OLSs specified by the VPS, is derived as follows:

(23) TABLE-US-00006 if(vps_max_layers_minus1 == 0) TotalNumOlss = 1 else if(each_layer_is_an_ols_flag || ols_mode_idc == 0 || ols_mode_idc == 1) TotalNumOlss = vps_max_layers_minus1 + 1 (39) else if(ols_mode_idc == 2) TotalNumOlss = num_output_layer_sets_minus1 + 1

ols_output_layer_flag[i][j] equal to 1 specifies that the layer with nuh_layer_id equal to vps_layer_id[j] is an output layer of the i-th OLS when ols_mode_idc is equal to 2. ols_output_layer_flag[i][j] equal to 0 specifies that the layer with nuh_layer_id equal to vps_layer_id[j] is not an output layer of the i-th OLS when ols_mode_idc is equal to 2.

The variable NumOutputLayersInOls[i], specifying the number of output layers in the i-th OLS, the variable NumSubLayersInLayerInOLS[i][j], specifying the number of sublayers in the j-th layer in the i-th OLS, the variable OutputLayerIdInOls[i][j], specifying the nuh_layer_id value of the j-th output layer in the i-th OLS, and the variable LayerUsedAsOutputLayerFlag[k], specifying whether the k-th layer is used as an output layer in at least one OLS, are derived as follows:

(24) TABLE-US-00007 NumOutputLayersInOls[0] = 1 OutputLayerIdInOls[0][0] = vps_layer_id[0] NumSubLayersInLayerInOLS[0][0] = vps_max_sub_layers_minus1 + 1 LayerUsedAsOutputLayerFlag[0] = 1 for(i = 1, i <= vps_max_layers_minus1; i++) { if(each_layer_is_an_ols_flag || ols_mode_idc < 2) LayerUsedAsOutputLayerFlag[i] = 1 else /*(!each_layer_is_an_ols_flag && ols_mode_idc == 2)*/ LayerUsedAsOutputLayerFlag[i] = 0 } for(i = 1; i < TotalNumOlss; i++) if(each_layer_is_an_ols_flag || ols_mode_idc == 0) { NumOutputLayersInOls[i] = 1 OutputLayerIdInOls[i][0] = vps_layer_id[i] for(j = 0; j < i && (ols_mode_idc == 0); j++) NumSubLayersInLayerInOLS[i][j] = max_tid_il_ref_pics_plus1[i] NumSubLayersInLayerInOLS[i][i] = vps_max_sub_layers_minus1 + 1 } else if(ols_mode_idc = 1) { NumOutputLayersInOls[i] = i + 1 for(j = 0, j < NumOutputLayersInOls[i], j++) { OutputLayerIdInOls[i][j] = vps_layer_id[j] NumSubLayersInLayerInOLS[i][j] = vps_max_sub_layers_minus1 + 1 } } else if(ols_mode_idc == 2) { for(j = 0; j <= vps_max_layers_minus1; j++) { layerIncludedInOlsFlag[i][j] = 0 NumSubLayersInLayerInOLS[i][j] = 0 } for(k = 0, j = 0; k <= vps_max_layers_minus1; k++) (40) if(ols_output_layer_flag[i][k]) { layerIncludedInOlsFlag[i][k] = 1 LayerUsedAsOutputLayerFlag[k] = 1 OutputLayerIdx[i][j] = k OutputLayerIdInOls[i][j++] = vps_layer_id[k] NumSubLayersInLayerInOLS[i][j] = vps_max_sub_layers_minus1 + 1 } NumOutputLayersInOls[i] = j for(j = 0; j < NumOutputLayersInOls[i]; j++) { idx = OutputLayerIdx[i][j] for(k = 0; k < NumRefLayers[idx]; k++) { layerIncludedInOlsFlag[1][RefLayerIdx[idx][k]] = 1 if(NumSubLayersInLayerInOLS[i][RefLayerIdx[idx][k]] < max_tid_il_ref_pics_plus1[OutputLayerIdInOls[i][j]]) NumSubLayersInLayerInOLS[i][RefLayerIdx[idx][k]] = max_tid_il_ref_pics_plus1[OutputLayerIdInOls[i][j]] } } }

For each value of i in the range of 0 to vps_max_layers_minus1, inclusive, the values of LayerUsedAsRefLayerFlag[i] and LayerUsedAsOutputLayerFlag[i] shall not be both equal to 0. In other words, there shall be no layer that is neither an output layer of at least one OLS nor a direct reference layer

of any other layer.

For each OLS, there shall be at least one layer that is an output layer. In other words, for any value of i in the range of 0 to $\text{TotalNumOlss}-1$, inclusive, the value of $\text{NumOutputLayersInOls}[i]$ shall be greater than or equal to 1.

The variable $\text{NumLayersInOls}[i]$, specifying the number of layers in the i -th OLS, and the variable $\text{LayerIdInOls}[i][j]$, specifying the nuh_layer_id value of the j -th layer in the i -th OLS, are derived as follows:

```
(25) TABLE-US-00008 NumLayersInOls[ 0 ] = 1 LayerIdInOls[ 0 ][ 0 ] = vps_layer_id[ 0 ] for( i = 1; i <
TotalNumOlss; i++ ) { if( each_layer_is_an_ols_flag ) { NumLayersInOls[ i ] = 1
LayerIdInOls[ i ][ 0 ] = vps_layer_id[ i ] (41) } else if( ols_mode_idc == 0 || ols_mode_idc == 1 ) {
NumLayersInOls[ i ] = i + 1 for( j = 0; j < NumLayersInOls[ i ]; j++ ) LayerIdInOls[ i ][
j ] = vps_layer_id[ j ] } else if( ols_mode_idc == 2 ) { for( k = 0, j = 0; k <=
vps_max_layers_minus1; k++ ) if( layerIncludedInOlsFlag[ i ][ k ] ) LayerIdInOls[ i ][ j++
] = vps_layer_id[ k ] NumLayersInOls[ i ] = j } }
```

The variable $\text{OlsLayerIdx}[i][j]$, specifying the OLS layer index of the layer with nuh_layer_id equal to $\text{LayerIdInOls}[i][j]$, is derived as follows:

```
(26) TABLE-US-00009 for( i = 0; i < TotalNumOlss; i++ ) for j = 0; j < NumLayersInOls[ i ]; j++ ) (42)
OlsLayerIdx[ i ][ LayerIdInOls[ i ][ j ] ] = j
```

The lowest layer in each OLS shall be an independent layer. In other words, for each i in the range of 0 to $\text{TotalNumOlss}-1$, inclusive, the value of $\text{vps_independent_layer_flag}[\text{GeneralLayerIdx}[\text{LayerIdInOls}[i][0]]]$ shall be equal to 1.

Each layer shall be included in at least one OLS specified by the VPS. In other words, for each layer with a particular value of nuh_layer_id nuhLayerId equal to one of $\text{vps_layer_id}[k]$ for k in the range of 0 to $\text{vps_max_layers_minus1}$, inclusive, there shall be at least one pair of values of i and j , where i is in the range of 0 to $\text{TotalNumOlss}-1$, inclusive, and j is in the range of $\text{NumLayersInOls}[i]-1$, inclusive, such that the value of $\text{LayerIdInOls}[i][j]$ is equal to nuhLayerId .

$\text{vps_num_ptls_minus1} + 1$ specifies the number of $\text{profile_tier_level}()$ syntax structures in the VPS.

The value of $\text{vps_num_ptls_minus1}$ shall be less than TotalNumOlss .

$\text{pt_present_flag}[i]$ equal to 1 specifies that profile, tier, and general constraints information are present in the i -th $\text{profile_tier_level}()$ syntax structure in the VPS. $\text{pt_present_flag}[i]$ equal to 0 specifies that profile, tier, and general constraints information are not present in the i -th $\text{profile_tier_level}()$ syntax structure in the VPS. The value of $\text{pt_present_flag}[0]$ is inferred to be equal to 1. When $\text{pt_present_flag}[i]$ is equal to 0, the profile, tier, and general constraints information for the i -th $\text{profile_tier_level}()$ syntax structure in the VPS are inferred to be the same as that for the $(i-1)$ -th $\text{profile_tier_level}()$ syntax structure in the VPS.

$\text{ptl_max_temporal_id}[i]$ specifies the TemporalId of the highest sublayer representation for which the level information is present in the i -th $\text{profile_tier_level}()$ syntax structure in the VPS. The value of $\text{ptl_max_temporal_id}[i]$ shall be in the range of 0 to $\text{vps_max_sublayers_minus1}$, inclusive. When $\text{vps_max_sublayers_minus1}$ is equal to 0, the value of $\text{ptl_max_temporal_id}[i]$ is inferred to be equal to 0. When $\text{vps_max_sublayers_minus1}$ is greater than 0 and $\text{vps_all_layers_same_num_sublayers_flag}$ is equal to 1, the value of $\text{ptl_max_temporal_id}[i]$ is inferred to be equal to $\text{vps_max_sublayers_minus1}$.

$\text{vps_ptl_alignment_zero_bit}$ shall be equal to 0.

$\text{ols_ptl_idx}[i]$ specifies the index, to the list of $\text{profile_tier_level}()$ syntax structures in the VPS, of the $\text{profile_tier_level}()$ syntax structure that applies to the i -th OLS. When present, the value of $\text{ols_ptl_idx}[i]$ shall be in the range of 0 to $\text{vps_num_ptls_minus1}$, inclusive. When $\text{vps_num_ptls_minus1}$ is equal to 0, the value of $\text{ols_ptl_idx}[i]$ is inferred to be equal to 0.

When $\text{NumLayersInOls}[i]$ is equal to 1, the $\text{profile_tier_level}()$ syntax structure that applies to the i -th OLS is also present in the SPS referred to by the layer in the i -th OLS. It is a requirement of bitstream conformance that, when $\text{NumLayersInOls}[i]$ is equal to 1, the $\text{profile_tier_level}()$ syntax structures signalled in the VPS and in the SPS for the i -th OLS shall be identical.

$\text{vps_num_dpb_params}$ specifies the number of $\text{dpb_parameters}()$ syntax structures in the VPS. The value of $\text{vps_num_dpb_params}$ shall be in the range of 0 to 16, inclusive. When not present, the value of $\text{vps_num_dpb_params}$ is inferred to be equal to 0.

`vps_sublayer_dpb_params_present_flag` is used to control the presence of `max_dec_pic_buffering_minus1[ ]`, `max_num_reorder_pics[ ]`, and `max_latency_increase_plus1[ ]` syntax elements in the `dpb_parameters( )` syntax structures in the VPS. When not present, `vps_sub_dpb_params_info_present_flag` is inferred to be equal to 0.

`dpb_max_temporal_id[i]` specifies the TemporalId of the highest sublayer representation for which the DPB parameters may be present in the *i*-th `dpb_parameters( )` syntax structure in the VPS. The value of `dpb_max_temporal_id[i]` shall be in the range of 0 to `vps_max_sublayers_minus1`, inclusive. When `vps_max_sublayers_minus1` is equal to 0, the value of `dpb_max_temporal_id[i]` is inferred to be equal to 0. When `vps_max_sublayers_minus1` is greater than 0 and `vps_all_layers_same_num_sublayers_flag` is equal to 1, the value of `dpb_max_temporal_id[i]` is inferred to be equal to `vps_max_sublayers_minus1`.

`ols_dpb_pic_width[i]` specifies the width, in units of luma samples, of each picture storage buffer for the *i*-th OLS.

`ols_dpb_pic_height[i]` specifies the height, in units of luma samples, of each picture storage buffer for the *i*-th OLS.

`ols_dpb_params_idx[i]` specifies the index, to the list of `dpb_parameters( )` syntax structures in the VPS, of the `dpb_parameters( )` syntax structure that applies to the *i*-th OLS when `NumLayersInOls[i]` is greater than 1. When present, the value of `ols_dpb_params_idx[i]` shall be in the range of 0 to `vps_num_dpb_params-1`, inclusive. When `ols_dpb_params_idx[i]` is not present, the value of `ols_dpb_params_idx[i]` is inferred to be equal to 0. When `NumLayersInOls[i]` is equal to 1, the `dpb_parameters( )` syntax structure that applies to the *i*-th OLS is present in the SPS referred to by the layer in the *i*-th OLS.

`vps_general_hrd_params_present_flag` equal to 1 specifies that the syntax structure `general_hrd_parameters( )` and other HRD parameters are present in the VPS RBSP syntax structure. `vps_general_hrd_params_present_flag` equal to 0 specifies that the syntax structure `general_hrd_parameters( )` and other HRD parameters are not present in the VPS RBSP syntax structure. When not present, the value of `vps_general_hrd_params_present_flag` is inferred to be equal to 0. When `NumLayersInOls[i]` is equal to 1, the `general_hrd_parameters( )` syntax structure that applies to the *i*-th OLS is present in the SPS referred to by the layer in the *i*-th OLS.

`vps_sublayer_cpb_params_present_flag` equal to 1 specifies that the *i*-th `ols_hrd_parameters( )` syntax structure in the VPS contains HRD parameters for the sublayer representations with TemporalId in the range of 0 to `hrd_max_tid[i]`, inclusive. `vps_sublayer_cpb_params_present_flag` equal to 0 specifies that the *i*-th `ols_hrd_parameters( )` syntax structure in the VPS contains HRD parameters for the sublayer representation with TemporalId equal to `hrd_max_tid[i]` only. When `vps_max_sublayers_minus1` is equal to 0, the value of `vps_sublayer_cpb_params_present_flag` is inferred to be equal to 0. When `vps_sublayer_cpb_params_present_flag` is equal to 0, the HRD parameters for the sublayer representations with TemporalId in the range of 0 to `hrd_max_tid[i]-1`, inclusive, are inferred to be the same as that for the sublayer representation with TemporalId equal to `hrd_max_tid[i]`. These include the HRD parameters starting from the `fixed_pic_rate_general_flag[i]` syntax element till the `sublayer_hrd_parameters(i)` syntax structure immediately under the condition “if(`general_vcl_hrd_params_present_flag`)” in the `ols_hrd_parameters` syntax structure.

`num_ols_hrd_params_minus1` plus 1 specifies the number of `ols_hrd_parameters( )` syntax structures present in the `general_hrd_parameters( )` syntax structure when `vps_general_hrd_params_present_flag` is equal to 1. The value of `num_ols_hrd_params_minus1` shall be in the range of 0 to `TotalNumOls-1`, inclusive.

`hrd_max_tid[i]` specifies the TemporalId of the highest sublayer representation for which the HRD parameters are contained in the *i*-th `ols_hrd_parameters( )` syntax structure. The value of `hrd_max_tid[i]` shall be in the range of 0 to `vps_max_sublayers_minus1`, inclusive. When `vps_max_sublayers_minus1` is equal to 0, the value of `hrd_max_tid[i]` is inferred to be equal to 0. When `vps_max_sublayers_minus1` is greater than 0 and `vps_all_layers_same_num_sublayers_flag` is equal to 1, the value of `hrd_max_tid[i]` is inferred to be equal to `vps_max_sublayers_minus1`.

`ols_hrd_idx[i]` specifies the index, to the list of `ols_hrd_parameters( )` syntax structures in the VPS, of the `ols_hrd_parameters( )` syntax structure that applies to the *i*-th OLS when `NumLayersInOls[i]` is greater than 1. The value of `ols_hrd_idx[i]` shall be in the range of 0 to `num_ols_hrd_params_minus1`, inclusive.

when NumLayersInOls[i] is equal to 1, the ols_hrd_parameters() syntax structure that applies to the i-th OLS is present in the SPS referred to by the layer in the i-th OLS.

If the value of num_ols_hrd_param_minus1+1 is equal to TotalNumOls, the value of ols_hrd_idx[i] is inferred to be equal to i. Otherwise, when NumLayersInOls[i] is greater than 1 and

num_ols_hrd_params_minus1 is equal to 0, the value of ols_hrd_idx[i] is inferred to be equal to 0.

vps_extension_flag equal to 0 specifies that no vps_extension_data_flag syntax elements are present in the VPS RBSP syntax structure. vps_extension_flag equal to 1 specifies that there are vps_extension_data_flag syntax elements present in the VPS RBSP syntax structure.

vps_extension_data_flag may have any value. Its presence and value do not affect decoder conformance to profiles specified in this version of this Specification. Decoders conforming to this version of this Specification shall ignore all vps_extension_data_flag syntax elements.

3.5. SPS Syntax and Semantics

In the latest VVC draft text, the SPS syntax and semantics are as follows:

```
(27) TABLE-US-00010 Descriptor seq_parameter_set_rbsp() {
    sps_seq_parameter_set_id u(4)
    sps_video_parameter_set_id u(4)    sps_max_sublayers_minus1 u(3)    sps_reserved_zero_4bits u(4)
    sps_ptl_dpb_hrd_params_present_flag u(1)    if( sps_ptl_dpb_hrd_params_present_flag )
    profile_tier_level( 1, sps_max_sublayers_minus1 )    gdr_enabled_flag u(1)    chroma_format_idc u(2)
    if( chroma_format_idc == 3 )    separate_colour_plane_flag u(1)
    res_change_in_clvs_allowed_flag u(1)    pic_width_max_in_luma_samples ue(v)
    pic_height_max_in_luma_samples ue(v)    sps_conformance_window_flag u(1)    if(
    sps_conformance_window_flag ) {    sps_conf_win_left_offset ue(v)    sps_conf_win_right_offset
    ue(v)    sps_conf_win_top_offset ue(v)    sps_conf_win_bottom_offset ue(v)    }
    sps_log2_ctu_size_minus5 u(2)    subpic_info_present_flag u(1)    if( subpic_info_present_flag ) {
    sps_num_subpics_minus1 ue(v)    sps_independent_subpics_flag u(1)    for( i = 0;
    sps_num_subpics_minus1 > 0 && i <= sps_num_subpics_minus1; i++ ) {    if( i > 0 &&
    pic_width_max_in_luma_samples > CtbSizeY )    subpic_ctu_top_left_x[ i ] u(v)    if( i > 0
    && pic_height_max_in_luma_samples > CtbSizeY ) {    subpic_ctu_top_left_y[ i ] u(v)
    if( i < sps_num_subpics_minus1 &&    pic_width_max_in_luma_samples > CtbSizeY )
    subpic_width_minus1[ i ] u(v)    if( i < sps_num_subpics_minus1 &&
    pic_height_max_in_luma_samples > CtbSizeY )    subpic_height_minus1[ i ] u(v)    if(
    !sps_independent_subpics_flag ) {    subpic_treated_as_pic_flag[ i ] u(1)
    loop_filter_across_subpic_enabled_flag[ i ] u(1)    }    }    sps_subpic_id_len_minus1 ue(v)
    subpic_id_mapping_explicitly_signalled_flag u(1)    if(
    subpic_id_mapping_explicitly_signalled_flag ) {    subpic_id_mapping_in_sps_flag u(1)    if(
    subpic_id_mapping_in_sps_flag )    for( i = 0; i <= sps_num_subpics_minus1; i++ )
    sps_subpic_id[ i ] u(v)    }    }    bit_depth_minus8 ue(v)    sps_entropy_coding_sync_enabled_flag
    u(1)    if( sps_entropy_coding_sync_enabled_flag )    sps_wpp_entry_point_offsets_present_flag u(1)
    sps_weighted_pred_flag u(1)    sps_weighted_bipred_flag u(1)
    log2_max_pic_order_cnt_lsb_minus4 u(4)    sps_poc_msb_flag u(1)    if( sps_poc_msb_flag )
    poc_msb_len_minus1 ue(v)    num_extra_ph_bits_bytes u(2)    extra_ph_bits_struct(
    num_extra_ph_bits_bytes )    num_extra_sh_bits_bytes u(2)    extra_sh_bits_struct(
    num_extra_sh_bits_bytes )    if( sps_max_sublayers_minus1 > 0 )    sps_sublayer_dpb_params_flag
    u(1)    if( sps_ptl_dpb_hrd_params_present_flag )    dpb_parameters( sps_max_sublayers_minus1,
    sps_sublayer_dpb_params_flag )    long_term_ref_pics_flag u(1)    inter_layer_ref_pics_present_flag
    u(1)    sps_idr_rpl_present_flag u(1)    rpl1_same_as_rpl0_flag u(1)    for( i = 0; i <
    !rpl1_same_as_rpl0_flag ? 2 : 1; i++ ) {    num_ref_pic_lists_in_sps[ i ] ue(v)    for( j = 0; j <
    num_ref_pic_lists_in_sps[ i ]; j++ )    ref_pic_list_struct( i, j )    }    if( ChromaArrayType != 0 )
    qtbtt_dual_tree_intra_flag u(1)    log2_min_luma_coding_block_size_minus2 ue(v)
    partition_constraints_override_enabled_flag u(1)    sps_log2_diff_min_qt_min_cb_intra_slice_luma
    ue(v)    if( sps_max_mtt_hierarchy_depth_intra_slice_luma != 0 ) {
    sps_log2_diff_max_bt_min_qt_intra_slice_luma ue(v)
    sps_log2_diff_max_tt_min_qt_intra_slice_luma ue(v)    }
    sps_log2_diff_min_qt_min_cb_inter_slice ue(v)    sps_max_mtt_hierarchy_depth_inter_slice ue(v)
```

```

if( sps_max_mtt_hierarchy_depth_intra_slice != 0 ) {
    sps_log2_diff_max_bt_min_qt_inter_slice ue(v)      sps_log2_diff_max_tt_min_qt_inter_slice ue(v)
    }      if( qtbtt_dual_tree_intra_flag ) {      sps_log2_diff_min_qt_min_cb_intra_slice_chroma
ue(v)      sps_max_mtt_hierarchy_depth_intra_slice_chroma ue(v)      if(
sps_max_mtt_hierarchy_depth_intra_slice_chroma != 0 ) {
    sps_log2_diff_max_bt_min_qt_intra_slice_chroma ue(v)
    sps_log2_diff_max_tt_min_qt_intra_slice_chroma ue(v)      }      }
    sps_max_luma_transform_size_64_flag u(1)      if ChromaArrayType != 0 ) {
    sps_joint_cbr_enabled_flag u(1)      same_qp_table_for_chroma u(1)      numQpTables =
same_qp_table_for_chroma ? 1 : ( sps_joint_cbr_enabled_flag ? 3 : 2 )      for(i = 0; i <
numQpTables: i++) {      qp_table_start_minus26[ i ] se(v)
    num_points_in_qp_table_minus1[ i ] ue(v)      for( j = 0; j <= num_points_in_qp_table_minus1[ i
]; j++ ) {      delta_qp_in_val_minus 1[ i ][ j ] ue(v)      delta_qp_diff_val[ i ][ j ] ue(v)
    }      }      }      sps_sao_enabled_flag u(1)      sps_alf_enabled_flag u(1)      if( sps_alf_enabled_flag
&& ChromaArrayType != 0 )      sps_ccalf_enabled_flag u(1)      sps_transform_skip_enabled_flag u(1)
    if( sps_transform_skip_enabled_flag ) {      log2_transform_skip_max_size_minus2 ue(v)
    sps_bdpcm_enabled_flag u(1)      }      sps_ref_wraparound_enabled_flag u(1)
    sps_temporal_mvp_enabled_flag u(1)      if( sps_temporal_mvp_enabled_flag )
    sps_sbtmvp_enabled_flag u(1)      sps_amvr_enabled_flag u(1)      sps_bdof_enabled_flag u(1)      if(
sps_bdof_enabled_flag )      sps_bdof_pic_present_flag u(1)      sps_smvd_enabled_flag u(1)
    sps_dmvr_enabled_flag u(1)      if( sps_dmvr_enabled_flag )      sps_dmvr_pic_present_flag u(1)
    sps_mmvd_enabled_flag u(1)      sps_isp_enabled_flag u(1)      sps_mrl_enabled_flag u(1)
    sps_mip_enabled_flag u(1)      if( ChromaArrayType != 0 )      sps_cclm_enabled_flag u(1)      if(
chroma_format_idc == 1 ) {      sps_chroma_horizontal_collocated_flag u(1)
    sps_chroma_vertical_collocated_flag u(1)      }      sps_mts_enabled_flag u(1)      if( sps_mts_enabled_flag )
    {      sps_explicit_mts_intra_enabled_flag u(1)      sps_explicit_mts_inter_enabled_flag u(1)      }
    six_minus_max_num_merge_cand ue(v)      sps_sbt_enabled_flag u(1)      sps_affine_enabled_flag u(1)
    if( sps_affine_enabled_flag ) {      five_minus_max_num_subblock_merge_cand ue(v)
    sps_affine_type_flag u(1)      if( sps_amvr_enabled_flag )      sps_affine_amvr_enabled_flag u(1)
    sps_affine_prof_enabled_flag u(1)      if( sps_affine_prof_enabled_flag )
    sps_prof_pic_present_flag u(1)      }      sps_palette_enabled_flag u(1)      if( ChromaArrayType == 3 &&
!sps_max_luma_transform_size_64_flag )      sps_act_enabled_flag u(1)      if(
sps_transform_skip_enabled_flag || sps_palette_enabled_flag )      min_qp_prime_ts_minus4 ue(v)
    sps_bcw_enabled_flag u(1)      sps_ibc_enabled_flag u(1)      if( sps_ibc_enabled_flag )
    six_minus_max_num_ibc_merge_cand ue(v)      sps_ciip_enabled_flag u(1)      if( sps_mmvd_enabled_flag
)      sps_fpel_mmvd_enabled_flag u(1)      if( MaxNumMergeCand >= 2 ) {      sps_gpm_enabled_flag
u(1)      if( sps_gpm_enabled_flag && MaxNumMergeCand >= 3 )
    max_num_merge_cand_minus_max_num_gpm_cand ue(v)      }      sps_lmcs_enabled_flag u(1)
    sps_lfnst_enabled_flag u(1)      sps_ladf_enabled_flag u(1)      if( sps_ladf_enabled_flag ) {
    sps_num_ladf_intervals_minus2 u(2)      sps_ladf_lowest_interval_qp_offset se(v)      for( i = 0; i <
sps_num_ladf_intervals_minus2 + 1; i++ ) {      sps_ladf_qp_offset[ i ] se(v)
    sps_ladf_delta_threshold_minus1[ i ] ue(v)      }      }      log2_parallel_merge_level_minus2 ue(v)
    sps_scaling_list_enabled_flag u(1)      sps_dep_quant_enabled_flag u(1)      if(
!sps_dep_quant_enabled_flag )      sps_sign_data_hiding_enabled_flag u(1)
    sps_virtual_boundaries_enabled_flag u(1)      if( sps_virtual_boundaries_enabled_flag ) {
    sps_virtual_boundaries_present_flag u(1)      if( sps_virtual_boundaries_present_flag ) {
    sps_num_ver_virtual_boundaries u(2)      for( i = 0; i < sps_num_ver_virtual_boundaries; i++ )
    sps_virtual_boundaries_pos_x[ i ] u(13)      sps_num_hor_virtual_boundaries u(2)
    for( i = 0; i < sps_num_hor_virtual_boundaries; i++ )      sps_virtual_boundaries_pos_y[ i ] u(13)
    }      }      if( sps_ptl_dpb_hrd_params_present_flag ) {      sps_general_hrd_params_present_flag
u(1)      if( sps_general_hrd_params_present_flag ) {      general_hrd_parameters( )      if(
sps_max_sublayers_minus1 > 0 )      sps_sublayer_cpb_params_present_flag u(1)
    firstSubLayer = sps_sublayer_cpb_params_present_flag ? 0 :      sps_max_sublayers_minus1

```

```

ols_hrd_parameters( firstSubLayer, sps_max_sublayers_minus1 )    } } field_seq_flag u(1)
vui_parameters_present_flag u(1)  if( vui_parameters_present_flag )  vui_parameters( ) /*
Specified in ITU-T H.264 | ISO/IEC 23002-7 */  sps_extension_flag u(1)  if( sps_extension_flag )
while( more_rbsp_data( ) )    sps_extension_data_flag u(1)  rbsp_trailing_bits( ) }

```

An SPS RBSP shall be available to the decoding process prior to it being referenced, included in at least one AU with TemporalId equal to 0 or provided through external means.

All SPS NAL units with a particular value of `sps_seq_parameter_set_id` in a CVS shall have the same content.

`sps_seq_parameter_set_id` provides an identifier for the SPS for reference by other syntax elements.

SPS NAL units, regardless of the `nuh_layer_id` values, share the same value space of

`sps_seq_parameter_set_id`. Let `spsLayerId` be the value of the `nuh_layer_id` of a particular SPS NAL unit, and `vclLayerId` be the value of the `nuh_layer_id` of a particular VCL NAL unit. The particular VCL NAL unit shall not refer to the particular SPS NAL unit unless `spsLayerId` is less than or equal to `vclLayerId` and the layer with `nuh_layer_id` equal to `spsLayerId` is included in at least one OLS that includes the layer with `nuh_layer_id` equal to `vclLayerId`.

`sps_video_parameter_set_id`, when greater than 0, specifies the value of `vps_video_parameter_set_id` for the VPS referred to by the SPS.

When `sps_video_parameter_set_id` is equal to 0, the following applies: The SPS does not refer to a VPS.

No VPS is referred to when decoding each CLVS referring to the SPS. The value of

`vps_max_layers_minus1` is inferred to be equal to 0. The CVS shall contain only one layer (i.e., all VCL NAL unit in the CVS shall have the same value of `nuh_layer_id`). The value of

`GeneralLayerIdx[nuh_layer_id]` is inferred to be equal to 0. The value of

`vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]]` is inferred to be equal to 1.

When `vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]]` is equal to 1, the SPS referred to by a CLVS with a particular `nuh_layer_id` value `nuhLayerId` shall have `nuh_layer_id` equal to `nuhLayerId`.

The value of `sps_video_parameter_set_id` shall be the same in all SPSs that are referred to by CLVSs in a CVS.

`sps_max_sublayers_minus1` plus 1 specifies the maximum number of temporal sublayers that may be present in each CLVS referring to the SPS. The value of `sps_max_sublayers_minus1` shall be in the range of 0 to `vps_max_sublayers_minus1`, inclusive.

`sps_reserved_zero_4` bits shall be equal to 0 in bitstreams conforming to this version of this Specification. Other values for `sps_reserved_zero_4` bits are reserved for future use by ITU-T|ISO/IEC.

`sps_ptl_dpb_hrd_params_present_flag` equal to 1 specifies that a `profile_tier_level( )` syntax structure and a `dpb_parameters( )` syntax structure are present in the SPS, and a `general_hrd_parameters( )` syntax structure and an `ols_hrd_parameters( )` syntax structure may also be present in the SPS.

`sps_ptl_dpb_hrd_params_present_flag` equal to 0 specifies that none of these four syntax structures is present in the SPS. The value of `sps_ptl_dpb_hrd_params_present_flag` shall be equal to `vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]]`.

`gdr_enabled_flag` equal to 1 specifies that GDR pictures may be present in CLVSs referring to the SPS.

`gdr_enabled_flag` equal to 0 specifies that GDR pictures are not present in CLVSs referring to the SPS.

`chroma_format_idc` specifies the chroma sampling relative to the luma sampling as specified in clause 6.2.

`separate_colour_plane_flag` equal to 1 specifies that the three color components of the 4:4:4 chroma format are coded separately. `separate_colour_plane_flag` equal to 0 specifies that the color components are not coded separately. When `separate_colour_plane_flag` is not present, it is inferred to be equal to 0. When `separate_colour_plane_flag` is equal to 1, the coded picture consists of three separate components, each of

which consists of coded samples of one color plane (Y, Cb, or Cr) and uses the monochrome coding syntax. In this case, each color plane is associated with a specific `colour_plane_id` value. NOTE 1—There is no dependency in decoding processes between the color planes having different `colour_plane_id` values.

For example, the decoding process of a monochrome picture with one value of `colour_plane_id` does not use any data from monochrome pictures having different values of `colour_plane_id` for inter prediction.

Depending on the value of `separate_colour_plane_flag`, the value of the variable `ChromaArrayType` is

assigned as follows: If `separate_colour_plane_flag` is equal to 0, `ChromaArrayType` is set equal to

`chroma_format_idc`. Otherwise (`separate_colour_plane_flag` is equal to 1), `ChromaArrayType` is set equal

to 0.

res_change_in_clvs_allowed_flag equal to 1 specifies that the picture spatial resolution may change within a CLVS referring to the SPS. res_change_in_clvs_allowed_flag equal to 0 specifies that the picture spatial resolution does not change within any CLVS referring to the SPS.

pic_width_max_in_luma_samples specifies the maximum width, in units of luma samples, of each decoded picture referring to the SPS. pic_width_max_in_luma_samples shall not be equal to 0 and shall be an integer multiple of $\text{Max}(8, \text{MinCbSizeY})$.

It is a requirement of bitstream conformance that, for any OLS with OLS index i that contains one or more layers that refers to the SPS, the value of pic_width_max_in_luma_samples shall be less than or equal to the value of $\text{ols_dpb_pic_width}[i]$.

pic_height_max_in_luma_samples specifies the maximum height, in units of luma samples, of each decoded picture referring to the SPS. pic_height_max_in_luma_samples shall not be equal to 0 and shall be an integer multiple of $\text{Max}(8, \text{MinCbSizeY})$.

It is a requirement of bitstream conformance that, for any OLS with OLS index i that contains one or more layers that refers to the SPS, the value of pic_height_max_in_luma_samples shall be less than or equal to the value of $\text{ols_dpb_pic_height}[i]$.

sps_conformance_window_flag equal to 1 indicates that the conformance cropping window offset parameters follow next in the SPS. sps_conformance_window_flag equal to 0 indicates that the conformance cropping window offset parameters are not present in the SPS.

sps_conf_win_left_offset, sps_conf_win_right_offset, sps_conf_win_top_offset, and sps_conf_win_bottom_offset specify the cropping window that is applied to pictures with pic_width_in_luma_samples equal to pic_width_max_in_luma_samples and pic_height_in_luma_samples equal to pic_height_max_in_luma_samples. When sps_conformance_window_flag is equal to 0, the values of sps_conf_win_left_offset, sps_conf_win_right_offset, sps_conf_win_top_offset, and sps_conf_win_bottom_offset are inferred to be equal to 0.

The conformance cropping window contains the luma samples with horizontal picture coordinates from $\text{SubWidthC} * \text{sps_conf_win_left_offset}$ to $\text{pic_width_max_in_luma_samples} - (\text{SubWidthC} * \text{sps_conf_win_right_offset} + 1)$ and vertical picture coordinates from $\text{SubHeightC} * \text{sps_conf_win_top_offset}$ to $\text{pic_height_max_in_luma_samples} - (\text{SubHeightC} * \text{sps_conf_win_bottom_offset} + 1)$, inclusive.

The value of $\text{SubWidthC} * (\text{sps_conf_win_left_offset} + \text{sps_conf_win_right_offset})$ shall be less than pic_width_max_in_luma_samples, and the value of $\text{SubHeightC} * (\text{sps_conf_win_top_offset} + \text{sps_conf_win_bottom_offset})$ shall be less than pic_height_max_in_luma_samples.

When ChromaArrayType is not equal to 0, the corresponding specified samples of the two chroma arrays are the samples having picture coordinates $(x/\text{SubWidthC}, y/\text{SubHeightC})$, where (x, y) are the picture coordinates of the specified luma samples. NOTE 2—The conformance cropping window offset parameters are only applied at the output. All internal decoding processes are applied to the uncropped picture size.

sps_log2_ctu_size_minus5 plus 5 specifies the luma coding tree block size of each CTU. The value of sps_log2_ctu_size_minus5 shall be in the range of 0 to 2, inclusive. The value 3 for sps_log2_ctu_size_minus5 is reserved for future use by ITU-T|ISO/IEC.

The variables CtbLog2SizeY and CtbSizeY are derived as follows:

$$\text{CtbLog2SizeY} = \text{sps_log2_ctu_size_minus5} + 5 \quad (43)$$

$$\text{CtbSizeY} = 1 \ll \text{CtbLog2SizeY} \quad (44)$$

subpic_info_present_flag equal to 1 specifies that subpicture information is present for the CLVS and there may be one or more than one subpicture in each picture of the CLVS. subpic_info_present_flag equal to 0 specifies that subpicture information is not present for the CLVS and there is only one subpicture in each picture of the CLVS. When res_change_in_clvs_allowed_flag is equal to 1, the value of subpic_info_present_flag shall be equal to 0. NOTE 3—When a bitstream is the result of a sub-bitstream extraction process and contains only a subset of the subpictures of the input bitstream to the sub-bitstream extraction process, it might be required to set the value of subpic_info_present_flag equal to 1 in the RBSP of the SPSs.

sps_num_subpics_minus1 plus 1 specifies the number of subpictures in each picture in the CLVS. The value of sps_num_subpics_minus1 shall be in the range of 0 to $\text{Ceil}(\text{pic_width_max_in_luma_samples} \times \text{CtbSizeY}) - 1$, inclusive. When not present, the value of sps_num_subpics_minus1 is inferred to be equal to 0.

sps_independent_subpics_flag equal to 1 specifies that no intra prediction, no inter prediction and no in-loop filtering operations may be performed across any subpicture boundary in the CLVS.

sps_independent_subpics_flag equal to 0 specifies that inter prediction or in-loop filtering operations across the subpicture boundaries in the CLVS may be allowed. When not present, the value of sps_independent_subpics_flag is inferred to be equal to 0.

subpic_ctu_top_left_x[i] specifies horizontal position of top left CTU of i-th subpicture in unit of CtbSizeY. The length of the syntax element is

$\text{Ceil}(\text{Log2}((\text{pic_width_max_in_luma_samples} + \text{CtbSizeY} - 1) \gg \text{CtbLog2SizeY}))$ bits. When not present, the value of subpic_ctu_top_left_x[i] is inferred to be equal to 0.

subpic_ctu_top_left_y[i] specifies vertical position of top left CTU of i-th subpicture in unit of CtbSizeY. The length of the syntax element is

$\text{Ceil}(\text{Log2}((\text{pic_height_max_in_luma_samples} + \text{CtbSizeY} - 1) \gg \text{CtbLog2SizeY}))$ bits. When not present, the value of subpic_ctu_top_left_y[i] is inferred to be equal to 0.

subpic_width_minus1 [i] plus 1 specifies the width of the i-th subpicture in units of CtbSizeY. The length of the syntax element is $\text{Ceil}(\text{Log2}((\text{pic_width_max_in_luma_samples} + \text{CtbSizeY} - 1) \gg \text{CtbLog2SizeY}))$ bits. When not present, the value of subpic_width_minus1[i] is inferred to be equal to

$((\text{pic_width_max_in_luma_samples} + \text{CtbSizeY} - 1) \gg \text{CtbLog2SizeY}) - \text{subpic_ctu_top_left_x}[i] - 1$.

subpic_height_minus1[i] plus 1 specifies the height of the i-th subpicture in units of CtbSizeY. The length of the syntax element is $\text{Ceil}(\text{Log2}((\text{pic_height_max_in_luma_samples} + \text{CtbSizeY} - 1) \gg \text{CtbLog2SizeY}))$ bits. When not present, the value of subpic_height_minus1[i] is inferred to be equal to

$((\text{pic_height_max_in_luma_samples} + \text{CtbSizeY} - 1) \gg \text{CtbLog2SizeY}) - \text{subpic_ctu_top_left_y}[i] - 1$.

subpic_treated_as_pic_flag[i] equal to 1 specifies that the i-th subpicture of each coded picture in the CLVS is treated as a picture in the decoding process excluding in-loop filtering operations.

subpic_treated_as_pic_flag[i] equal to 0 specifies that the i-th subpicture of each coded picture in the CLVS is not treated as a picture in the decoding process excluding in-loop filtering operations. When not present, the value of subpic_treated_as_pic_flag[i] is inferred to be equal to

sps_independent_subpics_flag.

When subpic_treated_as_pic_flag[i] is equal to 1, it is a requirement of bitstream conformance that all of the following conditions are true for each output layer and its reference layers in an OLS that includes the layer containing the i-th subpicture as an output layer: All pictures in the output layer and its reference layers shall have the same value of pic_width_in_luma_samples and the same value of

pic_height_in_luma_samples. All the SPSs referred to by the output layer and its reference layers shall have the same value of sps_num_subpics_minus1 and shall have the same values of

subpic_ctu_top_left_x[j], subpic_ctu_top_left_y[j], subpic_width_minus1[j], subpic_height_minus1[j], and loop_filter_across_subpic_enabled_flag[j], respectively, for each value of j in the range of 0 to sps_num_subpics_minus1, inclusive. All pictures in each access unit in the output layer and its reference layers shall have the same value of SubpicIdVal[j] for each value of j in the range of 0 to

sps_num_subpics_minus1, inclusive.

loop_filter_across_subpic_enabled_flag[i] equal to 1 specifies that in-loop filtering operations may be performed across the boundaries of the i-th subpicture in each coded picture in the CLVS.

loop_filter_across_subpic_enabled_flag[i] equal to 0 specifies that in-loop filtering operations are not performed across the boundaries of the i-th subpicture in each coded picture in the CLVS. When not present, the value of loop_filter_across_subpic_enabled_pic_flag[i] is inferred to be equal to $1 - \text{sps_independent_subpics_flag}$. It is a requirement of bitstream conformance that the shapes of the subpictures shall be such that each subpicture, when decoded, shall have its entire left boundary and entire top boundary consisting of picture boundaries or consisting of boundaries of previously decoded subpictures.

sps_subpic_id_len_minus1 plus 1 specifies the number of bits used to represent the syntax element sps_subpic_id[i], the syntax elements pps_subpic_id[i], when present, and the syntax element

slice_subpic_id, when present. The value of sps_subpic_id_len_minus1 shall be in the range of 0 to 15, inclusive. The value of $1 \leq (\text{sps_subpic_id_len_minus1} + 1)$ shall be greater than or equal to $\text{sps_num_subpics_minus1} + 1$.

subpic_id_mapping_explicitly_signalled_flag equal to 1 specifies that the subpicture ID mapping is explicitly signalled, either in the SPS or in the PPSs referred to by coded pictures of the CLVS.

subpic_id_mapping_explicitly_signalled_flag equal to 0 specifies that the subpicture ID mapping is not explicitly signalled for the CLVS. When not present, the value of

subpic_id_mapping_explicitly_signalled_flag is inferred to be equal to 0.

subpic_id_mapping_in_sps_flag equal to 1 specifies that the subpicture ID mapping is signalled in the SPS when subpic_id_mapping_explicitly_signalled_flag is equal to 1. subpic_id_mapping_in_sps_flag equal to 0 specifies that subpicture ID mapping is signalled in the PPSs referred to by coded pictures of the CLVS when subpic_id_mapping_explicitly_signalled_flag is equal to 1.

sps_subpic_id[i] specifies the subpicture ID of the i-th subpicture. The length of the sps_subpic_id[i] syntax element is $\text{sps_subpic_id_len_minus1} + 1$ bits.

bit_depth_minus8 specifies the bit depth of the samples of the luma and chroma arrays, BitDepth, and the value of the luma and chroma quantization parameter range offset, QpBdOffset, as follows:

$$\text{BitDepth} = 8 + \text{bit_depth_minus8} \quad (45)$$

$$\text{QpBdOffset} = 6 * \text{bit_depth_minus8} \quad (46)$$

bit_depth_minus8 shall be in the range of 0 to 8, inclusive.

sps_entropy_coding_sync_enabled_flag equal to 1 specifies that a specific synchronization process for context variables is invoked before decoding the CTU that includes the first CTB of a row of CTBs in each tile in each picture referring to the SPS, and a specific storage process for context variables is invoked after decoding the CTU that includes the first CTB of a row of CTBs in each tile in each picture referring to the SPS. sps_entropy_coding_sync_enabled_flag equal to 0 specifies that no specific synchronization process for context variables is required to be invoked before decoding the CTU that includes the first CTB of a row of CTBs in each tile in each picture referring to the SPS, and no specific storage process for context variables is required to be invoked after decoding the CTU that includes the first CTB of a row of CTBs in each tile in each picture referring to the SPS.

sps_wpp_entry_point_offsets_present_flag equal to 1 specifies that signalling for entry point offsets for CTU rows may be present in the slice headers of pictures referring to the SPS when

sps_entropy_coding_sync_enabled_flag is equal to 1. sps_wpp_entry_point_offsets_present_flag equal to 0 specifies that signalling for entry point offsets for CTU rows are not present in the slice headers of pictures referring to the SPS. When not present, the value of sps_wpp_entry_point_offsets_present_flag is inferred to be equal to 0.

sps_weighted_pred_flag equal to 1 specifies that weighted prediction may be applied to P slices referring to the SPS. sps_weighted_pred_flag equal to 0 specifies that weighted prediction is not applied to P slices referring to the SPS.

sps_weighted_bipred_flag equal to 1 specifies that explicit weighted prediction may be applied to B slices referring to the SPS. sps_weighted_bipred_flag equal to 0 specifies that explicit weighted prediction is not applied to B slices referring to the SPS.

log2_max_pic_order_cnt_lsb_minus4 specifies the value of the variable MaxPicOrderCntLsb that is used in the decoding process for picture order count as follows:

$$\text{MaxPicOrderCntLsb} = 2 * \text{sup.}(\log2_max_pic_order_cnt_lsb_minus4 + 4) \quad (47)$$

The value of log2_max_pic_order_cnt_lsb_minus4 shall be in the range of 0 to 12, inclusive.

sps_poc_msb_flag equal to 1 specifies that the ph_poc_msb_present_flag syntax element is present in PHs referring to the SPS. sps_poc_msb_flag equal to 0 specifies that the ph_poc_msb_present_flag syntax element is not present in PHs referring to the SPS.

poc_msb_len_minus1 plus 1 specifies the length, in bits, of the poc_msb_val syntax elements, when present in the PHs referring to the SPS. The value of poc_msb_len_minus1 shall be in the range of 0 to $32 - \log2_max_pic_order_cnt_lsb_minus4 - 5$, inclusive.

num_extra_ph_bits_bytes specifies the number of bytes of extra bits in the PH syntax structure for coded pictures referring to the SPS. The value of num_extra_ph_bits_bytes shall be equal to 0 in bitstreams conforming to this version of this Specification. Although the value of num_extra_ph_bits_bytes is

required to be equal to 0 in this version of this Specification, decoder conforming to this version of this Specification shall allow the value of num_extra_ph_bits_bytes equal to 1 or 2 to appear in the syntax. num_extra_sh_bits_bytes specifies the number of bytes of extra bits in the slice headers for coded pictures referring to the SPS. The value of num_extra_sh_bits_bytes shall be equal to 0 in bitstreams conforming to this version of this Specification. Although the value of num_extra_sh_bits_bytes is required to be equal to 0 in this version of this Specification, decoder conforming to this version of this Specification shall allow the value of num_extra_sh_bits_bytes equal to 1 or 2 to appear in the syntax.

sps_sublayer_dpb_params_flag is used to control the presence of max_dec_pic_buffering_minus1[i], max_num_reorder_pics[i], and max_latency_increase_plus1[i] syntax elements in the dpb_parameters() syntax structure in the SPS. When not present, the value of sps_sub_dpb_params_info_present_flag is inferred to be equal to 0.

long_term_ref_pics_flag equal to 0 specifies that no LTRP is used for inter prediction of any coded picture in the CLVS. long_term_ref_pics_flag equal to 1 specifies that LTRPs may be used for inter prediction of one or more coded pictures in the CLVS.

inter_layer_ref_pics_present_flag equal to 0 specifies that no ILRP is used for inter prediction of any coded picture in the CLVS. inter_layer_ref_pic_flag equal to 1 specifies that ILRPs may be used for inter prediction of one or more coded pictures in the CLVS. When sps_video_parameter_set_id is equal to 0, the value of inter_layer_ref_pics_present_flag is inferred to be equal to 0. When

vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]] is equal to 1, the value of inter_layer_ref_pics_present_flag shall be equal to 0. [Ed. (YK): Check whether there is a better name for this syntax element.]

sps_idr_rpl_present_flag equal to 1 specifies that reference picture list syntax elements are present in slice headers of IDR pictures. sps_idr_rpl_present_flag equal to 0 specifies that reference picture list syntax elements are not present in slice headers of IDR pictures.

rpl1_same_as_rpl0_flag equal to 1 specifies that the syntax element num_ref_pic_lists_in_sps[1] and the syntax structure ref_pic_list_struct(1, rplsIdx) are not present and the following applies: The value of num_ref_pic_lists_in_sps[1] is inferred to be equal to the value of num_ref_pic_lists_in_sps[0]. The value of each of syntax elements in ref_pic_list_struct(1, rplsIdx) is inferred to be equal to the value of corresponding syntax element in ref_pic_list_struct(0, rplsIdx) for rplsIdx ranging from 0 to num_ref_pic_lists_in_sps[0]-1.

num_ref_pic_lists_in_sps[i] specifies the number of the ref_pic_list_struct(listIdx, rplsIdx) syntax structures with listIdx equal to i included in the SPS. The value of num_ref_pic_lists_in_sps[i] shall be in the range of 0 to 64, inclusive. NOTE 4—For each value of listIdx (equal to 0 or 1), a decoder should allocate memory for a total number of num_ref_pic_lists_in_sps[i]+1 ref_pic_list_struct(listIdx, rplsIdx) syntax structures since there may be one ref_pic_list_struct(listIdx, rplsIdx) syntax structure directly signalled in the slice headers of a current picture.

qtbtt_dual_tree_intra_flag equal to 1 specifies that, for I slices, each CTU is split into coding units with 64×64 luma samples using an implicit quadtree split, and these coding units are the root of two separate coding_tree syntax structure for luma and chroma. qtbtt_dual_tree_intra_flag equal to 0 specifies separate coding_tree syntax structure is not used for I slices. When qtbtt_dual_tree_intra_flag is not present, it is inferred to be equal to 0.

log2_min_luma_coding_block_size_minus2 plus 2 specifies the minimum luma coding block size. The value range of log2_min_luma_coding_block_size_minus2 shall be in the range of 0 to Min(4, sps_log2_ctu_size_minus5+3), inclusive.

The variables MinCbLog2SizeY, MinCbSizeY, IbcBufWidthY, IbcBufWidthC and VSize are derived as follows:

$$\text{MinCbLog2SizeY} = \text{log2_min_luma_coding_block_size_minus2} + 2 \quad (48)$$

$$\text{MinCbSizeY} = 1 \ll \text{MinCbLog2SizeY} \quad (49)$$

$$\text{IbcBufWidthY} = 256 * 128 / \text{CtbSizeY} \quad (50)$$

$$\text{IbcBufWidthC} = \text{IbcBufWidthY} / \text{SubWidthC} \quad (51)$$

$$\text{VSize} = \text{Min}(64, \text{CtbSizeY}) \quad (52)$$

The value of MinCbSizeY shall less than or equal to VSize.

The variables CtbWidthC and CtbHeightC, which specify the width and height, respectively, of the array

for chroma_CTB, are derived as follows: If chroma_format_idc is equal to 0 (monochrome) or separate_colour_plane_flag is equal to 1, CtbWidthC and CtbHeightC are both equal to 0. Otherwise, CtbWidthC and CtbHeightC are derived as follows:

$$\text{CtbWidthC} = \text{CtbSizeY} / \text{SubWidthC} \quad (53)$$

$$\text{CtbHeightC} = \text{CtbSizeY} / \text{SubHeightC} \quad (54)$$

For log2BlockWidth ranging from 0 to 4 and for log2BlockHeight ranging from 0 to 4, inclusive, the up-right diagonal scan order array initialization process as specified in clause 6.5.2 is invoked with $1 < \log_2 \text{BlockWidth}$ and $1 < \log_2 \text{BlockHeight}$ as inputs, and the output is assigned to `DiagScanOrder[log2BlockWidth][log2BlockHeight]`.

For log2BlockWidth ranging from 0 to 6 and for log2BlockHeight ranging from 0 to 6, inclusive, the horizontal and vertical traverse scan order array initialization process as specified in clause 6.5.3 is invoked with $1 < \log_2 \text{BlockWidth}$ and $1 < \log_2 \text{BlockHeight}$ as inputs, and the output is assigned to `HorTravScanOrder[log2BlockWidth][log2BlockHeight]` and `VerTravScanOrder[log2BlockWidth][log2BlockHeight]`.

`partition_constraints_override_enabled_flag` equal to 1 specifies the presence of `partition_constraints_override_flag` in PHs referring to the SPS.

`partition_constraints_override_enabled_flag` equal to 0 specifies the absence of `partition_constraints_override_flag` in PHs referring to the SPS.

`sps_log2_diff_min_qt_min_cb_intra_slice_luma` specifies the default difference between the base 2 logarithm of the minimum size in luma samples of a luma leaf block resulting from quadtree splitting of a CTU and the base 2 logarithm of the minimum coding block size in luma samples for luma CUs in slices with `slice_type` equal to 2 (I) referring to the SPS. When `partition_constraints_override_enabled_flag` is equal to 1, the default difference can be overridden by `ph_log2_diff_min_qt_min_cb_luma` present in PHs referring to the SPS. The value of `sps_log2_diff_min_qt_min_cb_intra_slice_luma` shall be in the range of 0 to $\text{CtbLog}_2 \text{SizeY} - \text{MinCbLog}_2 \text{SizeY}$, inclusive. The base 2 logarithm of the minimum size in luma samples of a luma leaf block resulting from quadtree splitting of a CTU is derived as follows:

$$\text{MinQtLog}_2 \text{SizeIntraY} = \text{sps_log}_2 \text{_diff_min_qt_min_cb_intra_slice_luma} + \text{MinCbLog}_2 \text{SizeY} \quad (55)$$

`sps_max_mtt_hierarchy_depth_intra_slice_luma` specifies the default maximum hierarchy depth for coding units resulting from multi-type tree splitting of a quadtree leaf in slices with `slice_type` equal to 2 (I) referring to the SPS. When `partition_constraints_override_enabled_flag` is equal to 1, the default maximum hierarchy depth can be overridden by `ph_max_mtt_hierarchy_depth_intra_slice_luma` present in PHs referring to the SPS. The value of `sps_max_mtt_hierarchy_depth_intra_slice_luma` shall be in the range of 0 to $2 * (\text{CtbLog}_2 \text{SizeY} - \text{MinCbLog}_2 \text{SizeY})$, inclusive.

`sps_log2_diff_max_bt_min_qt_intra_slice_luma` specifies the default difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a luma coding block that can be split using a binary split and the minimum size (width or height) in luma samples of a luma leaf block resulting from quadtree splitting of a CTU in slices with `slice_type` equal to 2 (I) referring to the SPS. When `partition_constraints_override_enabled_flag` is equal to 1, the default difference can be overridden by `ph_log2_diff_max_bt_min_qt_luma` present in PHs referring to the SPS. The value of `sps_log2_diff_max_bt_min_qt_intra_slice_luma` shall be in the range of 0 to

$\text{CtbLog}_2 \text{SizeY} - \text{MinQtLog}_2 \text{SizeIntraY}$, inclusive. When `sps_log2_diff_max_bt_min_qt_intra_slice_luma` is not present, the value of `sps_log2_diff_max_bt_min_qt_intra_slice_luma` is inferred to be equal to 0.

`sps_log2_diff_max_tt_min_qt_intra_slice_luma` specifies the default difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a luma coding block that can be split using a ternary split and the minimum size (width or height) in luma samples of a luma leaf block resulting from quadtree splitting of a CTU in slices with `slice_type` equal to 2 (I) referring to the SPS.

When `partition_constraints_override_enabled_flag` is equal to 1, the default difference can be overridden by `ph_log2_diff_max_tt_min_qt_luma` present in PHs referring to the SPS. The value of `sps_log2_diff_max_tt_min_qt_intra_slice_luma` shall be in the range of 0 to

$\text{CtbLog}_2 \text{SizeY} - \text{MinQtLog}_2 \text{SizeIntraY}$, inclusive. When `sps_log2_diff_max_tt_min_qt_intra_slice_luma` is not present, the value of `sps_log2_diff_max_a_min_qt_intra_slice_luma` is inferred to be equal to 0.

`sps_log2_diff_min_qt_min_cb_inter_slice` specifies the default difference between the base 2 logarithm of the minimum size in luma samples of a luma leaf block resulting from quadtree splitting of a CTU and the

base 2 logarithm of the minimum luma coding block size in luma samples for luma CUs in slices with slice_type equal to 0 (B) or 1 (P) referring to the SPS. When partition_constraints_override_enabled_flag is equal to 1, the default difference can be overridden by ph_log2_diff_min_qt_min_cb_luma present in PHs referring to the SPS. The value of sps_log2_diff_min_qt_min_cb_inter_slice shall be in the range of 0 to CtbLog2SizeY-MinCbLog2SizeY, inclusive. The base 2 logarithm of the minimum size in luma samples of a luma leaf block resulting from quadtree splitting of a CTU is derived as follows:

$$\text{MinQtLog2SizeInterY} = \text{sps_log2_diff_min_qt_min_cb_inter_slice} + \text{MinCbLog2SizeY} \quad (56)$$

sps_max_mtt_hierarchy_depth_inter_slice specifies the default maximum hierarchy depth for coding units resulting from multi-type tree splitting of a quadtree leaf in slices with slice_type equal to 0 (B) or 1 (P) referring to the SPS. When partition_constraints_override_enabled_flag is equal to 1, the default maximum hierarchy depth can be overridden by ph_max_mtt_hierarchy_depth_inter_slice present in PHs referring to the SPS. The value of sps_max_mtt_hierarchy_depth_inter_slice shall be in the range of 0 to $2 * (\text{CtbLog2SizeY} - \text{MinCbLog2SizeY})$, inclusive.

sps_log2_diff_max_bt_min_qt_inter_slice specifies the default difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a luma coding block that can be split using a binary split and the minimum size (width or height) in luma samples of a luma leaf block resulting from quadtree splitting of a CTU in slices with slice_type equal to 0 (B) or 1 (P) referring to the SPS. When partition_constraints_override_enabled_flag is equal to 1, the default difference can be overridden by ph_log2_diff_max_bt_min_qt_luma present in PHs referring to the SPS. The value of

sps_log2_diff_max_bt_min_qt_inter_slice shall be in the range of 0 to

$\text{CtbLog2SizeY} - \text{MinQtLog2SizeInterY}$, inclusive. When sps_log2_diff_max_bt_min_qt_inter_slice is not present, the value of sps_log2_diff_max_bt_min_qt_inter_slice is inferred to be equal to 0.

sps_log2_diff_max_tt_min_qt_inter_slice specifies the default difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a luma coding block that can be split using a ternary split and the minimum size (width or height) in luma samples of a luma leaf block resulting from quadtree splitting of a CTU in slices with slice_type equal to 0 (B) or 1 (P) referring to the SPS. When partition_constraints_override_enabled_flag is equal to 1, the default difference can be overridden by ph_log2_diff_max_tt_min_qt_luma present in PHs referring to the SPS. The value of

sps_log2_diff_max_a_min_qt_inter_slice shall be in the range of 0 to

$\text{CtbLog2SizeY} - \text{MinQtLog2SizeInterY}$, inclusive. When sps_log2_diff_max_a_min_qt_inter_slice is not present, the value of sps_log2_diff_max_a_min_qt_inter_slice is inferred to be equal to 0.

sps_log2_diff_min_qt_min_cb_intra_slice_chroma specifies the default difference between the base 2 logarithm of the minimum size in luma samples of a chroma leaf block resulting from quadtree splitting of a chroma CTU with treeType equal to DUAL_TREE_CHROMA and the base 2 logarithm of the minimum coding block size in luma samples for chroma CUs with treeType equal to

DUAL_TREE_CHROMA in slices with slice_type equal to 2 (I) referring to the SPS. When

partition_constraints_override_enabled_flag is equal to 1, the default difference can be overridden by ph_log2_diff_min_qt_min_cb_chroma present in PHs referring to the SPS. The value of

sps_log2_diff_min_qt_min_cb_intra_slice_chroma shall be in the range of 0 to

$\text{CtbLog2SizeY} - \text{MinCbLog2SizeY}$, inclusive. When not present, the value of

sps_log2_diff_min_qt_min_cb_intra_slice_chroma is inferred to be equal to 0. The base 2 logarithm of the minimum size in luma samples of a chroma leaf block resulting from quadtree splitting of a CTU with treeType equal to DUAL_TREE_CHROMA is derived as follows:

$$\text{MinQtLog2SizeIntraC} = \text{sps_log2_diff_min_qt_min_cb_intra_slice_chroma} + \text{MinCbLog2SizeY} \quad (57)$$

sps_max_mtt_hierarchy_depth_intra_slice_chroma specifies the default maximum hierarchy depth for chroma coding units resulting from multi-type tree splitting of a chroma quadtree leaf with treeType equal to DUAL_TREE_CHROMA in slices with slice_type equal to 2 (I) referring to the SPS. When

partition_constraints_override_enabled_flag is equal to 1, the default maximum hierarchy depth can be overridden by ph_max_mtt_hierarchy_depth_chroma present in PHs referring to the SPS. The value of

sps_max_mtt_hierarchy_depth_intra_slice_chroma shall be in the range of 0 to $2 * (\text{CtbLog2SizeY} - \text{MinCbLog2SizeY})$, inclusive. When not present, the value of

sps_max_mtt_hierarchy_depth_intra_slice_chroma is inferred to be equal to 0.

sps_log2_diff_max_bt_min_qt_intra_slice_chroma specifies the default difference between the base 2

logarithm of the maximum size (width or height) in luma samples of a chroma coding block that can be split using a binary split and the minimum size (width or height) in luma samples of a chroma leaf block resulting from quadtree splitting of a chroma CTU with treeType equal to DUAL_TREE_CHROMA in slices with slice_type equal to 2 (I) referring to the SPS. When partition_constraints_override_enabled_flag is equal to 1, the default difference can be overridden by ph_log2_diff_max_bt_min_qt_chroma present in PHs referring to the SPS. The value of sps_log2_diff_max_bt_min_qt_intra_slice_chroma shall be in the range of 0 to CtbLog2SizeY-MinQtLog2SizeIntraC, inclusive. When sps_log2_diff_max_bt_min_qt_intra_slice_chroma is not present, the value of sps_log2_diff_max_bt_min_qt_intra_slice_chroma is inferred to be equal to 0. sps_log2_diff_max_tt_min_qt_intra_slice_chroma specifies the default difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a chroma coding block that can be split using a ternary split and the minimum size (width or height) in luma samples of a chroma leaf block resulting from quadtree splitting of a chroma CTU with treeType equal to DUAL_TREE_CHROMA in slices with slice_type equal to 2 (I) referring to the SPS. When partition_constraints_override_enabled_flag is equal to 1, the default difference can be overridden by ph_log2_diff_max_tt_min_qt_chroma present in PHs referring to the SPS. The value of sps_log2_diff_max_a_min_qt_intra_slice_chroma shall be in the range of 0 to CtbLog2SizeY-MinQtLog2SizeIntraC, inclusive. When sps_log2_diff_max_tt_min_qt_intra_slice_chroma is not present, the value of sps_log2_diff_max_a_min_qt_intra_slice_chroma is inferred to be equal to 0. sps_max_luma_transform_size_64_flag equal to 1 specifies that the maximum transform size in luma samples is equal to 64. sps_max_luma_transform_size_64_flag equal to 0 specifies that the maximum transform size in luma samples is equal to 32. When CtbSizeY is less than 64, the value of sps_max_luma_transform_size_64_flag shall be equal to 0. The variables MinTbLog2SizeY, MaxTbLog2SizeY, MinTbSizeY, and MaxTbSizeY are derived as follows:

$$\text{MinTbLog2SizeY}=2 \quad (58)$$

$$\text{MaxTbLog2SizeY}=\text{sps_max_luma_transform_size_64_flag?6:5} \quad (59)$$

$$\text{MinTbSizeY}=1<<\text{MinTbLog2SizeY} \quad (60)$$

$$\text{MaxTbSizeY}=1<<\text{MaxTbLog2SizeY} \quad (61)$$

sps_joint_eber_enabled_flag equal to 0 specifies that the joint coding of chroma residuals is disabled.

sps_joint_cbcr_enabled_flag equal to 1 specifies that the joint coding of chroma residuals is enabled.

When not present, the value of sps_joint_cbcr_enabled_flag is inferred to be equal to 0.

same_qp_table_for_chroma equal to 1 specifies that only one chroma QP mapping table is signalled and this table applies to Cb and Cr residuals and additionally to joint Cb-Cr residuals when

sps_joint_cbcr_enabled_flag is equal to 1. same_qp_table_for_chroma equal to 0 specifies that chroma QP mapping tables, two for Cb and Cr, and one additional for joint Cb-Cr when sps_joint_cbcr_enabled_flag is equal to 1, are signalled in the SPS. When same_qp_table_for_chroma is not present in the bitstream, the value of same_qp_table_for_chroma is inferred to be equal to 1.

qp_table_start_minus26[i] plus 26 specifies the starting luma and chroma QP used to describe the i-th chroma QP mapping table. The value of qp_table_start_minus26[i] shall be in the range of $\sim 26 - \text{QpBdOffset}$ to 36 inclusive. When qp_table_start_minus26[i] is not present in the bitstream, the value of qp_table_start_minus26[i] is inferred to be equal to 0.

num_points_in_qp_table_minus1[i] plus 1 specifies the number of points used to describe the i-th chroma QP mapping table. The value of num_points_in_qp_table_minus1[i] shall be in the range of 0 to $63 + \text{QpBdOffset}$, inclusive. When num_points_in_qp_table_minus1[0] is not present in the bitstream, the value of num_points_in_qp_table_minus1[0] is inferred to be equal to 0.

delta_qp_in_val_minus1[i][j] specifies a delta value used to derive the input coordinate of the j-th pivot point of the i-th chroma QP mapping table. When delta_qp_in_val_minus1[0][j] is not present in the bitstream, the value of delta_qp_in_val_minus1[0][j] is inferred to be equal to 0.

delta_qp_diff_val[i][j] specifies a delta value used to derive the output coordinate of the j-th pivot point of the i-th chroma QP mapping table.

The i-th chroma QP mapping table $\text{ChromaQpTable}[i]$ for $i=0 \dots \text{numQpTables}-1$ is derived as follows:

```

(28) TABLE-US-00011
qpInVal[ i ][ 0 ] = qp_table_start_minus26[ i ] + 26
qpOutVal[ i ][ 0 ] = qpInVal[ i ][ 0 ]
for( j = 0; j <= num_points_in_qp_table_minus1[ i ]; j++ ) {
    qpInVal[ i ][ j + 1 ] = qpInVal[ i ][ j ]
    + delta_qp_in_val_minus1[ i ][ j ] + 1
    qpOutVal[ i ][ j + 1 ] = qpOutVal[ i ][ j ] + (
    delta_qp_in_val_minus1[ i ][ j ] {circumflex over ( )} delta_qp_diff_val[ i ][ j ] )
}
ChromaQpTable[ i ][ qpInVal[ i ][ 0 ] ] = qpOutVal[ i ][ 0 ]
for( k = qpInVal[ i ][ 0 ] - 1; k >= -QpBdOffset, k -- )
ChromaQpTable[ i ][ k ] = Clip3( -QpBdOffset, 63, ChromaQpTable[ i ][ k + 1 ] - 1 )
for( j = 0; j <= num_points_in_qp_table_minus1[ i ]; j++ ) {
    sh = ( delta_qp_in_val_minus1[ i ][ j ] + 1 ) >> 1
    for( k = qpInVal[ i ][ j ] + 1, m = 1; k <= qpInVal[ i ][ j + 1 ]; k++, m++ )
        ChromaQpTable[ i ][ k ]
        = ChromaQpTable[ i ][ qpInVal[ i ][ j ] ] +
        ( ( qpOutVal[ i ][ j + 1 ] - qpOutVal[ i ][ j ] ) * m + sh ) / (
        delta_qp_in_val_minus1[ i ][ j ] + 1 )
    }
    for( k = qpInVal[ i ][ num_points_in_qp_table_minus1[ i ] + 1 ] + 1; k <= 63, k++ )
        ChromaQpTable[ i ][ k ] = Clip3( -QpBdOffset, 63, ChromaQpTable[ i ][ k - 1 ] + 1 )

```

When $\text{same_qp_table_for_chroma}$ is equal to 1, $\text{ChromaQpTable}[1][k]$ and $\text{ChromaQpTable}[2][k]$ are set equal to $\text{ChromaQpTable}[0][k]$ for k in the range of $-\text{QpBdOffset}$ to 63, inclusive.

It is a requirement of bitstream conformance that the values of $\text{qpInVal}[i][j]$ and $\text{qpOutVal}[i][j]$ shall be in the range of $-\text{QpBdOffset}$ to 63, inclusive for i in the range of 0 to $\text{numQpTables}-1$, inclusive, and j in the range of 0 to $\text{num_points_in_qp_table_minus1}[i]+1$, inclusive.

$\text{sps_sao_enabled_flag}$ equal to 1 specifies that the sample adaptive offset process is applied to the reconstructed picture after the deblocking filter process. $\text{sps_sao_enabled_flag}$ equal to 0 specifies that the sample adaptive offset process is not applied to the reconstructed picture after the deblocking filter process.

$\text{sps_alf_enabled_flag}$ equal to 0 specifies that the adaptive loop filter is disabled. $\text{sps_alf_enabled_flag}$ equal to 1 specifies that the adaptive loop filter is enabled.

$\text{sps_ccalf_enabled_flag}$ equal to 0 specifies that the cross-component adaptive loop filter is disabled.

$\text{sps_ccalf_enabled_flag}$ equal to 1 specifies that the cross-component adaptive loop filter may be enabled.

$\text{sps_transform_skip_enabled_flag}$ equal to 1 specifies that $\text{transform_skip_flag}$ may be present in the transform unit syntax. $\text{sps_transform_skip_enabled_flag}$ equal to 0 specifies that $\text{transform_skip_flag}$ is not present in the transform unit syntax.

$\text{log2_transform_skip_max_size_minus2}$ specifies the maximum block size used for transform skip, and shall be in the range of 0 to 3, inclusive.

The variable MaxTsSize is set equal to $1 << (\text{log2_transform_skip_max_size_minus2} + 2)$.

$\text{sps_bdpcm_enabled_flag}$ equal to 1 specifies that $\text{intra_bdpcm_luma_flag}$ and $\text{intra_bdpcm_chroma_flag}$ may be present in the coding unit syntax for intra coding units. $\text{sps_bdpcm_enabled_flag}$ equal to 0 specifies that $\text{intra_bdpcm_luma_flag}$ and $\text{intra_bdpcm_chroma_flag}$ are not present in the coding unit syntax for intra coding units. When not present, the value of $\text{sps_bdpcm_enabled_flag}$ is inferred to be equal to 0.

$\text{sps_ref_wraparound_enabled_flag}$ equal to 1 specifies that horizontal wrap-around motion compensation is applied in inter prediction. $\text{sps_ref_wraparound_enabled_flag}$ equal to 0 specifies that horizontal wrap-around motion compensation is not applied. When the value of $(\text{CtbSizeY}/\text{MinCbSizeY} + 1)$ is greater than $(\text{pic_width_in_luma_samples}/\text{MinCbSizeY} - 1)$, where $\text{pic_width_in_luma_samples}$ is the value of $\text{pic_width_in_luma_samples}$ in any PPS that refers to the SPS, the value of

$\text{sps_ref_wraparound_enabled_flag}$ shall be equal to 0. [Ed. (YK): The semantics here still depends on PPS syntax elements.]

$\text{sps_temporal_mvp_enabled_flag}$ equal to 1 specifies that temporal motion vector predictors may be used in the CLVS. $\text{sps_temporal_mvp_enabled_flag}$ equal to 0 specifies that temporal motion vector predictors are not used in the CLVS.

$\text{sps_sbtmvp_enabled_flag}$ equal to 1 specifies that subblock-based temporal motion vector predictors may be used in decoding of pictures with all slices having slice_type not equal to 1 in the CLVS.

$\text{sps_sbtmvp_enabled_flag}$ equal to 0 specifies that subblock-based temporal motion vector predictors are not used in the CLVS. When $\text{sps_sbtmvp_enabled_flag}$ is not present, it is inferred to be equal to 0.

$\text{sps_amvr_enabled_flag}$ equal to 1 specifies that adaptive motion vector difference resolution is used in motion vector coding. amvr_enabled_flag equal to 0 specifies that adaptive motion vector difference

resolution is not used in motion vector coding.

sps_bdof_enabled_flag equal to 0 specifies that the bi-directional optical flow inter prediction is disabled.

sps_bdof_enabled_flag equal to 1 specifies that the bi-directional optical flow inter prediction is enabled.

sps_bdof_pic_present_flag equal to 1 specifies that ph_disable_bdof_flag is present in PHs referring to the SPS. sps_bdof_pic_present_flag equal to 0 specifies that ph_disable_bdof_flag is not present in PHs referring to the SPS. When sps_bdof_pic_present_flag is not present, the value of sps_bdof_pic_present_flag is inferred to be equal to 0.

sps_smvd_enabled_flag equal to 1 specifies that symmetric motion vector difference may be used in motion vector decoding. sps_smvd_enabled_flag equal to 0 specifies that symmetric motion vector difference is not used in motion vector coding.

sps_dmvr_enabled_flag equal to 1 specifies that decoder motion vector refinement based inter bi-prediction is enabled. sps_dmvr_enabled_flag equal to 0 specifies that decoder motion vector refinement based inter bi-prediction is disabled.

sps_dmvr_pic_present_flag equal to 1 specifies that ph_disable_dmvr_flag is present in PHs referring to the SPS. sps_dmvr_pic_present_flag equal to 0 specifies that ph_disable_dmvr_flag is not present in PHs referring to the SPS. When sps_dmvr_pic_present_flag is not present, the value of sps_dmvr_pic_present_flag is inferred to be equal to 0.

sps_mmvd_enabled_flag equal to 1 specifies that merge mode with motion vector difference is enabled.

sps_mmvd_enabled_flag equal to 0 specifies that merge mode with motion vector difference is disabled.

sps_isp_enabled_flag equal to 1 specifies that intra prediction with subpartitions is enabled.

sps_isp_enabled_flag equal to 0 specifies that intra prediction with subpartitions is disabled.

sps_mrl_enabled_flag equal to 1 specifies that intra prediction with multiple reference lines is enabled.

sps_mrl_enabled_flag equal to 0 specifies that intra prediction with multiple reference lines is disabled.

sps_mip_enabled_flag equal to 1 specifies that matrix-based intra prediction is enabled.

sps_mip_enabled_flag equal to 0 specifies that matrix-based intra prediction is disabled.

sps_cclm_enabled_flag equal to 0 specifies that the cross-component linear model intra prediction from luma component to chroma component is disabled. sps_cclm_enabled_flag equal to 1 specifies that the cross-component linear model intra prediction from luma component to chroma component is enabled. When sps_cclm_enabled_flag is not present, it is inferred to be equal to 0.

sps_chroma_horizontal_collocated_flag equal to 1 specifies that prediction processes operate in a manner designed for chroma sample positions that are not horizontally shifted relative to corresponding luma sample positions. sps_chroma_horizontal_collocated_flag equal to 0 specifies that prediction processes operate in a manner designed for chroma sample positions that are shifted to the right by 0.5 in units of luma samples relative to corresponding luma sample positions. When

sps_chroma_horizontal_collocated_flag is not present, it is inferred to be equal to 1.

sps_chroma_vertical_collocated_flag equal to 1 specifies that prediction processes operate in a manner designed for chroma sample positions that are not vertically shifted relative to corresponding luma sample positions. sps_chroma_vertical_collocated_flag equal to 0 specifies that prediction processes operate in a manner designed for chroma sample positions that are shifted downward by 0.5 in units of luma samples relative to corresponding luma sample positions. When sps_chroma_vertical_collocated_flag is not present, it is inferred to be equal to 1.

sps_mts_enabled_flag equal to 1 specifies that sps_explicit_mts_intra_enabled_flag is present in the sequence parameter set RBSP syntax and sps_explicit_mts_inter_enabled_flag is present in the sequence parameter set RBSP syntax. sps_mts_enabled_flag equal to 0 specifies that

sps_explicit_mts_intra_enabled_flag is not present in the sequence parameter set RBSP syntax and sps_explicit_mts_inter_enabled_flag is not present in the sequence parameter set RBSP syntax.

sps_explicit_mts_intra_enabled_flag equal to 1 specifies that mts_idx may be present in intra coding unit syntax. sps_explicit_mts_intra_enabled_flag equal to 0 specifies that mts_idx is not present in intra coding unit syntax. When not present, the value of sps_explicit_mts_intra_enabled_flag is inferred to be equal to 0.

sps_explicit_mts_inter_enabled_flag equal to 1 specifies that mts_idx may be present in inter coding unit syntax. sps_explicit_mts_inter_enabled_flag equal to 0 specifies that mts_idx is not present in inter coding unit syntax. When not present, the value of sps_explicit_mts_inter_enabled_flag is inferred to be equal to

0.

six_minus_max_num_merge_cand specifies the maximum number of merging motion vector prediction (MVP) candidates supported in the SPS subtracted from 6. The value of six_minus_max_num_merge_cand shall be in the range of 0 to 5, inclusive.

The maximum number of merging MVP candidates, MaxNumMergeCand, is derived as follows:

$$\text{MaxNumMergeCand} = 6 - \text{six_minus_max_num_merge_cand} \quad (63)$$

sps_sbt_enabled_flag equal to 0 specifies that subblock transform for inter-predicted CUs is disabled.

sps_sbt_enabled_flag equal to 1 specifies that subblock transform for inter-predicted CU is enabled.

sps_affine_enabled_flag specifies whether affine model based motion compensation can be used for inter prediction. If sps_affine_enabled_flag is equal to 0, the syntax shall be constrained such that no affine model based motion compensation is used in the CLVS, and inter_affine_flag and cu_affine_type_flag are not present in coding unit syntax of the CLVS. Otherwise (sps_affine_enabled_flag is equal to 1), affine model based motion compensation can be used in the CLVS.

five_minus_max_num_subblock_merge_cand specifies the maximum number of subblock-based merging motion vector prediction candidates supported in the SPS subtracted from 5.

sps_affine_type_flag specifies whether 6-parameter affine model based motion compensation can be used for inter prediction. If sps_affine_type_flag is equal to 0, the syntax shall be constrained such that no 6-parameter affine model based motion compensation is used in the CLVS, and cu_affine_type_flag is not present in coding unit syntax in the CLVS. Otherwise (sps_affine_type_flag is equal to 1), 6-parameter affine model based motion compensation can be used in the CLVS. When not present, the value of sps_affine_type_flag is inferred to be equal to 0.

sps_affine_amvr_enabled_flag equal to 1 specifies that adaptive motion vector difference resolution is used in motion vector coding of affine inter mode. sps_affine_amvr_enabled_flag equal to 0 specifies that adaptive motion vector difference resolution is not used in motion vector coding of affine inter mode.

When not present, the value of sps_affine_amvr_enabled_flag is inferred to be equal to 0.

sps_affine_prof_enabled_flag specifies whether the prediction refinement with optical flow can be used for affine motion compensation. If sps_affine_prof_enabled_flag is equal to 0, the affine motion compensation shall not be refined with optical flow. Otherwise (sps_affine_prof_enabled_flag is equal to 1), the affine motion compensation can be refined with optical flow. When not present, the value of sps_affine_prof_enabled_flag is inferred to be equal to 0.

sps_prof_pic_present_flag equal to 1 specifies that ph_disable_prof_flag is present in PHs referring to the SPS. sps_prof_pic_present_flag equal to 0 specifies that ph_disable_prof_flag is not present in PHs referring to the SPS. When sps_prof_pic_present_flag is not present, the value of sps_prof_pic_present_flag is inferred to be equal to 0.

sps_palette_enabled_flag equal to 1 specifies that pred_mode_plt_flag may be present in the coding unit syntax. sps_palette_enabled_flag equal to 0 specifies that pred_mode_plt_flag is not present in the coding unit syntax. When sps_palette_enabled_flag is not present, it is inferred to be equal to 0.

sps_act_enabled_flag equal to 1 specifies that adaptive color transform may be used and the cu_act_enabled_flag may be present in the coding unit syntax. sps_act_enabled_flag equal to 0 specifies that adaptive color transform is not used and cu_act_enabled_flag is not present in the coding unit syntax. When sps_act_enabled_flag is not present, it is inferred to be equal to 0.

min_qp_prime_ts_minus4 specifies the minimum allowed quantization parameter for transform skip mode as follows:

$$\text{QpPrimeTsMin} = 4 + \text{min_qp_prime_ts_minus4} \quad (64)$$

The value of min_qp_prime_ts_minus4 shall be in the range of 0 to 48, inclusive.

sps_bcw_enabled_flag specifies whether bi-prediction with CU weights can be used for inter prediction. If sps_bcw_enabled_flag is equal to 0, the syntax shall be constrained such that no bi-prediction with CU weights is used in the CLVS, and bcw_idx is not present in coding unit syntax of the CLVS. Otherwise (sps_bcw_enabled_flag is equal to 1), bi-prediction with CU weights can be used in the CLVS.

sps_ibc_enabled_flag equal to 1 specifies that the IBC prediction mode may be used in decoding of pictures in the CLVS. sps_ibc_enabled_flag equal to 0 specifies that the IBC prediction mode is not used in the CLVS. When sps_ibc_enabled_flag is not present, it is inferred to be equal to 0.

six_minus_max_num_ibc_merge_cand specifies the maximum number of IBC merging block vector

prediction (BVP) candidates supported in the SPS subtracted from 6. The value of

six_minus_max_num_ibc_merge_cand shall be in the range of 0 to 5, inclusive.

The maximum number of IBC merging BVP candidates, MaxNumIbcMergeCand, is derived as follows:

(29) TABLE-US-00012 if(sps_ibc_enabled_flag) MaxNumIbcMergeCand = 6 – (65)

six_minus_max_num_ibc_merge_cand else MaxNumIbcMergeCand = 0

sps_ciip_enabled_flag specifies that ciip_flag may be present in the coding unit syntax for inter coding units. sps_ciip_enabled_flag equal to 0 specifies that ciip_flag is not present in the coding unit syntax for inter coding units.

sps_fpel_mmvd_enabled_flag equal to 1 specifies that merge mode with motion vector difference is using integer sample precision. sps_fpel_mmvd_enabled_flag equal to 0 specifies that merge mode with motion vector difference can use fractional sample precision.

sps_gpm_enabled_flag specifies whether geometric partition based motion compensation can be used for inter prediction. sps_gpm_enabled_flag equal to 0 specifies that the syntax shall be constrained such that no geometric partition based motion compensation is used in the CLVS, and merge_gpm_partition_idx, merge_gpm_idx0, and merge_gpm_idx1 are not present in coding unit syntax of the CLVS.

sps_gpm_enabled_flag equal to 1 specifies that geometric partition based motion compensation can be used in the CLVS. When not present, the value of sps_gpm_enabled_flag is inferred to be equal to 0.

max_num_merge_cand_minus_max_num_gpm_cand specifies the maximum number of geometric partitioning merge mode candidates supported in the SPS subtracted from MaxNumMergeCand.

The maximum number of geometric partitioning merge mode candidates, MaxNumGpmMergeCand, is derived as follows:

(30) TABLE-US-00013 if(sps_gpm_enabled_flag && MaxNumMergeCand >= 3)

MaxNumGpmMergeCand = MaxNumMergeCand –

max_num_merge_cand_minus_max_num_gpm_cand (66) else if(sps_gpm_enabled_flag && MaxNumMergeCand == 2) MaxNumMergeCand = 2 else MaxNumGpmMergeCand = 0

(31) The value of MaxNumGpmMergeCand shall be in the range of 2 to MaxNumMergeCand, inclusive.

(32) sps_lmcs_enabled_flag equal to 1 specifies that luma mapping with chroma scaling is used in the CLVS. sps_lmcs_enabled_flag equal to 0 specifies that luma mapping with chroma scaling is not used in the CLVS.

(33) sps_lfnst_enabled_flag equal to 1 specifies that lfnst_idx may be present in intra coding unit syntax.

sps_lfnst_enabled_flag equal to 0 specifies that lfnst_idx is not present in intra coding unit syntax.

(34) sps_ladf_enabled_flag equal to 1, specifies that sps_num_ladf_intervals_minus2, sps_ladf_lowest_interval_qp_offset, sps_ladf_qp_offset[i], and sps_ladf_delta_threshold_minus1[i] are present in the SPS.

(35) sps_num_ladf_intervals_minus2 plus 1 specifies the number of sps_ladf_delta_threshold_minus1[i] and sps_ladf_qp_offset[i] syntax elements that are present in the SPS. The value of sps_num_ladf_intervals_minus2 shall be in the range of 0 to 3, inclusive.

(36) sps_ladf_lowest_interval_qp_offset specifies the offset used to derive the variable qP as specified in clause 8.8.3.6.1. The value of sps_ladf_lowest_interval_qp_offset shall be in the range of –63 to 63, inclusive.

(37) sps_ladf_qp_offset[i] specifies the offset array used to derive the variable qP as specified in clause 8.8.3.6.1. The value of sps_ladf_qp_offset[i] shall be in the range of –63 to 63, inclusive.

(38) sps_ladf_delta_threshold_minus1 [i] is used to compute the values of SpsLadfIntervalLowerBound[i], which specifies the lower bound of the i-th luma intensity level interval. The value of sps_ladf_delta_threshold_minus1[i] shall be in the range of 0 to 2 BitDepth 3, inclusive. The value of SpsLadfIntervalLowerBound[0] is set equal to 0.

For each value of i in the range of 0 to sps_num_ladf_intervals_minus2, inclusive, the variable

SpsLadfIntervalLowerBound[i+1] is derived as follows:

SpsLadfIntervalLowerBound[i+1]=SpsLadfIntervalLowerBound[i]+sps_ladf_delta_threshold_minus1[i]+1 (67)

log2_parallel_merge_level_minus2 plus 2 specifies the value of the variable Log2ParMrgLevel, which is used in the derivation process for spatial merging candidates as specified in clause 8.5.2.3, the derivation process for motion vectors and reference indices in subblock merge mode as specified in clause 8.5.5.2,

and to control the invocation of the updating process for the history-based motion vector predictor list in clause 8.5.2.1. The value of `log2_parallel_merge_level_minus2` shall be in the range of 0 to `CtbLog2SizeY-2`, inclusive. The variable `Log2ParMrgLevel` is derived as follows:

$\text{Log2ParMrgLevel} = \text{log2_parallel_merge_level_minus2} + 2 \quad (68)$

`sps_scaling_list_enabled_flag` equal to 1 specifies that a scaling list is used for the scaling process for transform coefficients. `sps_scaling_list_enabled_flag` equal to 0 specifies that scaling list is not used for the scaling process for transform coefficients.

`sps_dep_quant_enabled_flag` equal to 0 specifies that dependent quantization is disabled for pictures referring to the SPS. `sps_dep_quant_enabled_flag` equal to 1 specifies that dependent quantization may be enabled for pictures referring to the SPS.

`sps_sign_data_hiding_enabled_flag` equal to 0 specifies that sign bit hiding is disabled for pictures referring to the SPS. `sps_sign_data_hiding_enabled_flag` equal to 1 specifies that sign bit hiding may be enabled for pictures referring to the SPS. When `sps_sign_data_hiding_enabled_flag` is not present, it is inferred to be equal to 0.

`sps_virtual_boundaries_enabled_flag` equal to 1 specifies that disabling in-loop filtering across virtual boundaries may be applied in the coded pictures in the CLVS. `sps_virtual_boundaries_enabled_flag` equal to 0 specifies that disabling in-loop filtering across virtual boundaries is not applied in the coded pictures in the CLVS. In-loop filtering operations include the deblocking filter, sample adaptive offset filter, and adaptive loop filter operations.

`sps_virtual_boundaries_present_flag` equal to 1 specifies that information of virtual boundaries is signalled in the SPS. `sps_virtual_boundaries_present_flag` equal to 0 specifies that information of virtual boundaries is not signalled in the SPS. When there is one or more than one virtual boundaries signalled in the SPS, the in-loop filtering operations are disabled across the virtual boundaries in pictures referring to the SPS. In-loop filtering operations include the deblocking filter, sample adaptive offset filter, and adaptive loop filter operations. It is a requirement of bitstream conformance that when the value of `res_change_in_clvs_allowed_flag` is equal to 1, the value of `sps_virtual_boundaries_present_flag` shall be equal to 0.

`sps_num_ver_virtual_boundaries` specifies the number of `sps_virtual_boundaries_pos_x[i]` syntax elements that are present in the SPS. When `sps_num_ver_virtual_boundaries` is not present, it is inferred to be equal to 0.

`sps_virtual_boundaries_pos_x[i]` specifies the location of the *i*-th vertical virtual boundary in units of luma samples divided by 8. The value of `sps_virtual_boundaries_pos_x[i]` shall be in the range of 1 to $\text{Ceil}(\text{pic_width_in_luma_samples} \div 8) - 1$, inclusive. [Ed. (VD): `pic_width_in_luma_samples` is in the PPS, not in the SPS.]

`sps_num_hor_virtual_boundaries` specifies the number of `sps_virtual_boundaries_pos_y[i]` syntax elements that are present in the SPS. When `sps_num_hor_virtual_boundaries` is not present, it is inferred to be equal to 0. When `sps_virtual_boundaries_enabled_flag` is equal to 1 and

`sps_virtual_boundaries_present_flag` is equal to 1, the sum of `sps_num_ver_virtual_boundaries` and `sps_num_hor_virtual_boundaries` shall be greater than 0.

`sps_virtual_boundaries_pos_y[i]` specifies the location of the *i*-th horizontal virtual boundary in units of luma samples divided by 8. The value of `sps_virtual_boundaries_pos_y[i]` shall be in the range of 1 to $\text{Ceil}(\text{pic_height_in_luma_samples} \div 8) - 1$, inclusive. [Ed. (VD): `pic_height_in_luma_samples` is in the PPS, not in the SPS.]

`sps_general_hrd_params_present_flag` equal to 1 specifies that the syntax structure `general_hrd_parameters()` is present in the SPS RBSP syntax structure.

`sps_general_hrd_params_present_flag` equal to 0 specifies that the syntax structure `general_hrd_parameters()` is not present in the SPS RBSP syntax structure.

`sps_sublayer_cpb_params_present_flag` equal to 1 specifies that the syntax structure `old_hrd_parameters()` in the SPS RBSP includes HRD parameters for sublayer representations with `TemporalId` in the range of 0 to `sps_max_sublayers_minus1`, inclusive. `sps_sublayer_cpb_params_present_flag` equal to 0 specifies that the syntax structure `ols_hrd_parameters()` in the SPS RBSP includes HRD parameters for the sublayer representation with `TemporalId` equal to `sps_max_sublayers_minus1` only. When `sps_max_sublayers_minus1` is equal to 0, the value of `sps_sublayer_cpb_params_present_flag` is inferred

to be equal to 0.

When `sps_sublayer_cpb_params_present_flag` is equal to 0, the HRD parameters for the sublayer representations with `TemporalId` in the range of 0 to `sps_max_sublayers_minus1`–1, inclusive, are inferred to be the same as that for the sublayer representation with `TemporalId` equal to `sps_max_sublayers_minus1`. These include the HRD parameters starting from the `fixed_pic_rate_general_flag[i]` syntax element till the `sublayer_hrd_parameters(i)` syntax structure immediately under the condition “if(`general_vcl_hrd_params_present_flag`)” in the `ols_hrd_parameters` syntax structure.

`field_seq_flag` equal to 1 indicates that the CLVS conveys pictures that represent fields. `field_seq_flag` equal to 0 indicates that the CLVS conveys pictures that represent frames. When

`general_frame_only_constraint_flag` is equal to 1, the value of `field_seq_flag` shall be equal to 0.

When `field_seq_flag` is equal to 1, a frame-field information SEI message shall be present for every coded picture in the CLVS. NOTE 5—The specified decoding process does not treat pictures that represent fields or frames differently. A sequence of pictures that represent fields would therefore be coded with the picture dimensions of an individual field. For example, pictures that represent 1080i fields would commonly have cropped output dimensions of 1920×540, while the sequence picture rate would commonly express the rate of the source fields (typically between 50 and 60 Hz), instead of the source frame rate (typically between 25 and 30 Hz).

`vui_parameters_present_flag` equal to 1 specifies that the syntax structure `vui_parameters()` is present in the SPS RBSP syntax structure. `vui_parameters_present_flag` equal to 0 specifies that the syntax structure `vui_parameters()` is not present in the SPS RBSP syntax structure.

`sps_extension_flag` equal to 0 specifies that no `sps_extension_data_flag` syntax elements are present in the SPS RBSP syntax structure. `sps_extension_flag` equal to 1 specifies that there are `sps_extension_data_flag` syntax elements present in the SPS RBSP syntax structure.

`sps_extension_data_flag` may have any value. Its presence and value do not affect decoder conformance to profiles specified in this version of this Specification. Decoders conforming to this version of this Specification shall ignore all `sps_extension_data_flag` syntax elements.

3.6. PPS Syntax and Semantics

In the latest VVC draft text, the PPS syntax and semantics are as follows:

```
(39) TABLE-US-00014 Descriptor pic_parameter_set_rbsp() {
    pps_pic_parameter_set_id ue(v)
    pps_seq_parameter_set_id u(4)
    mixed_nalu_types_in_pic_flag u(1)
    pic_width_in_luma_samples ue(v)
    pic_height_in_luma_samples ue(v)
    pps_conformance_window_flag u(1)
    if( pps_conformance_window_flag ) {
        pps_conf_win_left_offset ue(v)
        pps_conf_win_right_offset ue(v)
        pps_conf_win_top_offset ue(v)
        pps_conf_win_bottom_offset ue(v)
    }
    scaling_window_explicit_signalling_flag u(1)
    if( scaling_window_explicit_signalling_flag ) {
        scaling_win_left_offset ue(v)
        scaling_win_right_offset ue(v)
        scaling_win_top_offset ue(v)
        scaling_win_bottom_offset ue(v)
    }
    output_flag_present_flag u(1)
    subpic_id_mapping_in_pps_flag u(1)
    if( subpic_id_mapping_in_pps_flag ) {
        pps_num_subpics_minus1 ue(v)
        pps_subpic_id_len_minus1 ue(v)
        for( i = 0; i <= pps_num_subpic_minus1; i++ )
            pps_subpic_id[ i ] u(v)
    }
    no_pic_partition_flag u(1)
    if( !no_pic_partition_flag ) {
        pps_log2_ctu_size_minus5 u(2)
        num_exp_tile_columns_minus1 ue(v)
        num_exp_tile_rows_minus1 ue(v)
        for( i = 0; i <= num_exp_tile_columns_minus1; i++ )
            tile_column_width_minus1[ i ] ue(v)
        for( i = 0; i <= num_exp_tile_rows_minus1; i++ )
            tile_row_height_minus1[ i ] ue(v)
        if( NumTilesInPic > 1 )
            rect_slice_flag u(1)
        if( rect_slice_flag )
            single_slice_per_subpic_flag u(1)
        if( rect_slice_flag && !single_slice_per_subpic_flag ) {
            num_slices_in_pic_minus1 ue(v)
            if( num_slices_in_pic_minus1 > 0 )
                tile_idx_delta_present_flag u(1)
            for( i = 0; i < num_slices_in_pic_minus1; i++ ) {
                if( NumTileColumns > 1 )
                    slice_width_in_tiles_minus1[ i ] ue(v)
                if( NumTileRows > 1 && ( tile_idx_delta_present_flag || tileIdx % NumTileColumns == 0 ) )
                    slice_height_in_tiles_minus1[ i ] ue(v)
                if( slice_width_in_tiles_minus1[ i ] == 0 && slice_height_in_tiles_minus1[ i ] == 0 && RowHeight[ SliceTopLeftTileIdx[ i ] / NumTileColumns ] > 1 ) {
                    num_exp_slices_in_tile[

```

```

i ] ue(v)      for( j = 0; j < num_exp_slices_in_tile[ i ]; j++ )
exp_slice_height_in_ctus_minus1[ j ] ue(v)      i += NumSlicesInTile[ i ] - 1      }
      if( tile_idx_delta_present_flag && i < num_slices_in_pic_minus1 )
tile_idx_delta[ i ] se(v)      }      }      loop_filter_across_tiles_enabled_flag u(1)
loop_filter_across_slices_enabled_flag u(1)      }      cabac_init_present_flag u(1)      for( i = 0; i < 2; i++ )
      num_ref_idx_default_active_minus1[ i ] ue(v)      rpl1_idx_present_flag u(1)      init_qp_minus26
se(v)      cu_qp_delta_enabled_flag u(1)      pps_chroma_tool_offsets_present_flag u(1)      if(
pps_chroma_tool_offsets_present_flag ) {      pps_cb_qp_offset se(v)      pps_cr_qp_offset se(v)
pps_joint_cbr_qp_offset_present_flag u(1)      if( pps_joint_cbr_qp_offset_present_flag )
pps_joint_cbr_qp_offset_value se(v)      pps_slice_chroma_qp_offsets_present_flag u(1)
pps_cu_chroma_qp_offset_list_enabled_flag u(1)      }      if( pps_cu_chroma_qp_offset_list_enabled_flag
) {      chroma_qp_offset_list_len_minus1 ue(v)      for( i = 0; i <=
chroma_qp_offset_list_len_minus1; i++ ) {      cb_qp_offset_list[i ] se(v)
cr_qp_offset_list[i ] se(v)      if( pps_joint_cbr_qp_offset_present_flag )
joint_cbr_qp_offset_list[ i ] se(v)      }      }      pps_weighted_pred_flag u(1)
pps_weighted_bipred_flag u(1)      deblocking_filter_control_present_flag u(1)      if(
deblocking_filter_control_present_flag ) {      deblocking_filter_override_enabled_flag u(1)
pps_deblocking_filter_disabled_flag u(1)      if( !pps_deblocking_filter_disabled_flag ) {
pps_beta_offset_div2 se(v)      pps_tc_offset_div2 se(v)      pps_cb_beta_offset_div2 se(v)
      pps_cb_tc_offset_div2 se(v)      pps_cr_beta_offset_div2 se(v)      pps_cr_tc_offset_div2
se(v)      }      }      rpl_info_in_ph_flag u(1)      if( deblocking_filter_override_enabled_flag )
dbf_info_in_ph_flag u(1)      sao_info_in_ph_flag u(1)      alf_info_in_ph_flag u(1)      if( (
pps_weighted_pred_flag || pps_weighted_bipred_flag ) && rpl_info_in_ph_flag )
wp_info_in_ph_flag u(1)      qp_delta_info_in_ph_flag u(1)      pps_ref_wraparound_enabled_flag u(1)
if( pps_ref_wraparound_enabled_flag )      pps_ref_wraparound_offset ue(v)
picture_header_extension_present_flag u(1)      slice_header_extension_present_flag u(1)
pps_extension_flag u(1)      if( pps_extension_flag )      while( more_rbsp_data( ) )
pps_extension_data_flag u(1)      rbsp_trailing_bits( ) }

```

A PPS RBSP shall be available to the decoding process prior to it being referenced, included in at least one AU with TemporalId less than or equal to the TemporalId of the PPS NAL unit or provided through external means.

All PPS NAL units with a particular value of `pps_pic_parameter_set_id` within a PU shall have the same content. `pps_pic_parameter_set_id` identifies the PPS for reference by other syntax elements. The value of `pps_pic_parameter_set_id` shall be in the range of 0 to 63, inclusive.

PPS NAL units, regardless of the `nuh_layer_id` values, share the same value space of `pps_pic_parameter_set_id`. Let `ppsLayerId` be the value of the `nuh_layer_id` of a particular PPS NAL unit, and `vclLayerId` be the value of the `nuh_layer_id` of a particular VCL NAL unit. The particular VCL NAL unit shall not refer to the particular PPS NAL unit unless `ppsLayerId` is less than or equal to `vclLayerId` and the layer with `nuh_layer_id` equal to `ppsLayerId` is included in at least one OLS that includes the layer with `nuh_layer_id` equal to `vclLayerId`.

`pps_seq_parameter_set_id` specifies the value of `sps_seq_parameter_set_id` for the SPS. The value of `pps_seq_parameter_set_id` shall be in the range of 0 to 15, inclusive. The value of `pps_seq_parameter_set_id` shall be the same in all PPSs that are referred to by coded pictures in a CLVS. `mixed_nalu_types_in_pic_flag` equal to 1 specifies that each picture referring to the PPS has more than one VCL NAL unit, the VCL NAL units do not have the same value of `nal_unit_type`, and the picture is not an TRAP picture. `mixed_nalu_types_in_pic_flag` equal to 0 specifies that each picture referring to the PPS has one or more VCL NAL units and the VCL NAL units of each picture referring to the PPS have the same value of `nal_unit_type`.

When `no_mixed_nalu_types_in_pic_constraint_flag` is equal to 1, the value of `mixed_nalu_types_in_pic_flag` shall be equal to 0.

For each slice with a `nal_unit_type` value `nalUnitTypeA` in the range of IDR_W_RADL to CRA_NUT, inclusive, in a picture `picA` that also contains one or more slices with another value of `nal_unit_type` (i.e., the value of `mixed_nalu_types_in_pic_flag` for the picture `picA` is equal to 1), the following applies: The

slice shall belong to a subpicture subpicA for which the value of the corresponding subpic_treated_as_pic_flag[i] is equal to 1. The slice shall not belong to a subpicture of picA containing VCL NAL units with nal_unit_type not equal to nalUnitTypeA. If nalUnitTypeA is equal to CRA, for all the following PUs following the current picture in the CLVS in decoding order and in output order, neither RefPicList[0] nor RefPicList[1] of a slice in subpicA in those PUs shall include any picture preceding picA in decoding order in an active entry. Otherwise (i.e., nalUnitTypeA is equal to IDR_W_RADL or IDR_N_LP), for all the PUs in the CLVS following the current picture in decoding order, neither RefPicList[0] nor RefPicList[1] of a slice in subpicA in those PUs shall include any picture preceding picA in decoding order in an active entry. NOTE 1—mixed_nalu_types_in_pic_flag equal to 1 indicates that pictures referring to the PPS contain slices with different NAL unit types, e.g., coded pictures originating from a subpicture bitstream merging operation for which encoders have to ensure matching bitstream structure and further alignment of parameters of the original bitstreams. One example of such alignments is as follows: When the value of sps_idr_rpl_flag is equal to 0 and mixed_nalu_types_in_pic_flag is equal to 1, a picture referring to the PPS cannot have slices with nal_unit_type equal to IDR_W_RADL or IDR_N_LP.

pic_width_in_luma_samples specifies the width of each decoded picture referring to the PPS in units of luma samples. pic_width_in_luma_samples shall not be equal to 0, shall be an integer multiple of Max(8, MinCbSizeY), and shall be less than or equal to pic_width_max_in_luma_samples.

When res_change_in_clvs_allowed_flag equal to 0, the value of pic_width_in_luma_samples shall be equal to pic_width_max_in_luma_samples.

pic_height_in_luma_samples specifies the height of each decoded picture referring to the PPS in units of luma samples. pic_height_in_luma_samples shall not be equal to 0 and shall be an integer multiple of Max(8, MinCbSizeY), and shall be less than or equal to pic_height_max_in_luma_samples.

When res_change_in_clvs_allowed_flag equal to 0, the value of pic_height_in_luma_samples shall be equal to pic_height_max_in_luma_samples.

The variables PicWidthInCtbsY, PicHeightInCtbsY, PicSizeInCtbsY, PicWidthInMinCbsY, PicHeightInMinCbsY, PicSizeInMinCbsY, PicSizeInSamplesY, PicWidthInSamplesC and PicHeightInSamplesC are derived as follows:

$$\text{PicWidthInCtbsY} = \text{Ceil}(\text{pic_width_in_luma_samples} \cdot \text{CtbSizeY}) \quad (69)$$

$$\text{PicHeightInCtbsY} = \text{Ceil}(\text{pic_height_in_luma_samples} \cdot \text{CtbSizeY}) \quad (70)$$

$$\text{PicSizeInCtbsY} = \text{PicWidthInCtbsY} \cdot \text{PicHeightInCtbsY} \quad (71)$$

$$\text{PicWidthInMinCbsY} = \text{pic_width_in_luma_samples} / \text{MinCbSizeY} \quad (72)$$

$$\text{PicHeightInMinCbsY} = \text{pic_height_in_luma_samples} / \text{MinCbSizeY} \quad (73)$$

$$\text{PicSizeInMinCbsY} = \text{PicWidthInMinCbsY} \cdot \text{PicHeightInMinCbsY} \quad (74)$$

$$\text{PicSizeInSamplesY} = \text{pic_width_in_luma_samples} \cdot \text{pic_height_in_luma_samples} \quad (75)$$

$$\text{PicWidthInSamplesC} = \text{pic_width_in_luma_samples} / \text{SubWidthC} \quad (76)$$

$$\text{PicHeightInSamplesC} = \text{pic_height_in_luma_samples} / \text{SubHeightC} \quad (77)$$

pps_conformance_window_flag equal to 1 indicates that the conformance cropping window offset parameters follow next in the PPS. pps_conformance_window_flag equal to 0 indicates that the conformance cropping window offset parameters are not present in the PPS.

pps_conf_win_left_offset, pps_conf_win_right_offset, pps_conf_win_top_offset, and pps_conf_win_bottom_offset specify the samples of the pictures in the CLVS that are output from the decoding process, in terms of a rectangular region specified in picture coordinates for output. When pps_conformance_window_flag is equal to 0, the values of pps_conf_win_left_offset, pps_conf_win_right_offset, pps_conf_win_top_offset, and pps_conf_win_bottom_offset are inferred to be equal to 0.

The conformance cropping window contains the luma samples with horizontal picture coordinates from SubWidthC*pps_conf_win_left_offset to pic_width_in_luma_samples-(SubWidthC*pps_conf_win_right_offset+1) and vertical picture coordinates from SubHeightC*pps_conf_win_top_offset to pic_height_in_luma_samples-(SubHeightC*pps_conf_win_bottom_offset+1), inclusive.

The value of SubWidthC*(pps_conf_win_left_offset+pps_conf_win_right_offset) shall be less than pic_width_in_luma_samples, and the value of SubHeightC*

(pps_conf_win_top_offset+pps_conf_win_bottom_offset) shall be less than pic_height_in_luma_samples. When ChromaArrayType is not equal to 0, the corresponding specified samples of the two chroma arrays are the samples having picture coordinates (x/SubWidthC, y/SubHeightC), where (x, y) are the picture coordinates of the specified luma samples. NOTE 2—The conformance cropping window offset parameters are only applied at the output. All internal decoding processes are applied to the uncropped picture size.

Let ppsA and ppsB be any two PPSs referring to the same SPS. It is a requirement of bitstream conformance that, when ppsA and ppsB have the same the values of pic_width_in_luma_samples and pic_height_in_luma_samples, respectively, ppsA and ppsB shall have the same values of pps_conf_win_left_offset, pps_conf_win_right_offset, pps_conf_win_top_offset, and pps_conf_win_bottom_offset, respectively.

When pic_width_in_luma_samples is equal to pic_width_max_in_luma_samples and pic_height_in_luma_samples is equal to pic_height_max_in_luma_samples, it is a requirement of bitstream conformance that pps_conf_win_left_offset, pps_conf_win_right_offset, pps_conf_win_top_offset, and pps_conf_win_bottom_offset, are equal to sps_conf_win_left_offset, sps_conf_win_right_offset, sps_conf_win_top_offset, and sps_conf_win_bottom_offset, respectively. scaling_window_explicit_signalling_flag equal to 1 specifies that the scaling window offset parameters are present in the PPS. scaling_window_explicit_signalling_flag equal to 0 specifies that the scaling window offset parameters are not present in the PPS. When res_change_in_clvs_allowed_flag is equal to 0, the value of scaling_window_explicit_signalling_flag shall be equal to 0.

scaling_win_left_offset, scaling_win_right_offset, scaling_win_top_offset, and scaling_win_bottom_offset specify the offsets that are applied to the picture size for scaling ratio calculation. When not present, the values of scaling_win_left_offset, scaling_win_right_offset, scaling_win_top_offset, and scaling_win_bottom_offset are inferred to be equal to pps_conf_win_left_offset, pps_conf_win_right_offset, pps_conf_win_top_offset, and pps_conf_win_bottom_offset, respectively.

The value of SubWidthC*(scaling_win_left_offset+scaling_win_right_offset) shall be less than pic_width_in_luma_samples, and the value of SubHeightC*(scaling_win_top_offset+scaling_win_bottom_offset) shall be less than pic_height_in_luma_samples. The variables PicOutputWidthL and PicOutputHeightL are derived as follows:

$$\text{PicOutputWidthL} = \text{pic_width_in_luma_samples} - \text{SubWidthC} * (\text{scaling_win_right_offset} + \text{scaling_win_left_offset}) \quad (78)$$

$$\text{PicOutputHeightL} = \text{pic_height_in_luma_samples} - \text{SubHeightC} * (\text{scaling_win_bottom_offset} + \text{scaling_win_top_offset}) \quad (79)$$

Let refPicOutputWidthL and refPicOutputHeightL be the PicOutputWidthL and PicOutputHeightL, respectively, of a reference picture of a current picture referring to this PPS. Is a requirement of bitstream conformance that all of the following conditions are satisfied: PicOutputWidthL*2 shall be greater than or equal to refPicWidthInLumaSamples. PicOutputHeightL*2 shall be greater than or equal to refPicHeightInLumaSamples. PicOutputWidthL shall be less than or equal to refPicWidthInLumaSamples*8. PicOutputHeightL shall be less than or equal to refPicHeightInLumaSamples*8. PicOutputWidthL*pic_width_max_in_luma_samples shall be greater than or equal to refPicOutputWidthL*(pic_width_in_luma_samples-Max(8, MinCbSizeY)). PicOutputHeightL*pic_height_max_in_luma_samples shall be greater than or equal to refPicOutputHeightL*(pic_height_in_luma_samples-Max(8, MinCbSizeY)).

output_flag_present_flag equal to 1 indicates that the pic_output_flag syntax element is present in slice headers referring to the PPS. output_flag_present_flag equal to 0 indicates that the pic_output_flag syntax element is not present in slice headers referring to the PPS.

subpic_id_mapping_in_pps_flag equal to 1 specifies that the subpicture ID mapping is signalled in the PPS. subpic_id_mapping_in_pps_flag equal to 0 specifies that the subpicture ID mapping is not signalled in the PPS. If subpic_id_mapping_explicitly_signalled_flag is 0 or subpic_id_mapping_in_pps_flag is equal to 1, the value of subpic_id_mapping_in_pps_flag shall be equal to 0. Otherwise (subpic_id_mapping_explicitly_signalled_flag is equal to 1 and subpic_id_mapping_in_sps_flag is equal to 0), the value of subpic_id_mapping_in_pps_flag shall be equal to 1.

pps_num_subpics_minus1 shall be equal to sps_num_subpics_minus1.

pps_subpic_id_len_minus1 shall be equal to sps_subpic_id_len_minus1.

pps_subpic_id[i] specifies the subpicture ID of the i-th subpicture. The length of the pps_subpic_id[i] syntax element is pps_subpic_id_len_minus1+1 bits.

The variable SubpicIdVal[i], for each value of i in the range of 0 to sps_num_subpics_minus1, inclusive, is derived as follows:

(40) TABLE-US-00015 for(i = 0; i <= sps_num_subpics_minus1; i++) if(subpic_id_mapping_explicitly_signalled_flag) SubpicIdVal[i] = subpic_id_mapping_in_pps_flag ? pps_subpic_id[i] : sps_subpic_id[j] (80) else SubpicIdVal[i] = i

It is a requirement of bitstream conformance that both of the following constraints apply: For any two different values of i and j in the range of 0 to sps_num_subpics_minus1, inclusive, SubpicIdVal[i] shall not be equal to SubpicIdVal[j]. When the current picture is not the first picture of the CLVS, for each value of i in the range of 0 to sps_num_subpics_minus1, inclusive, if the value of SubpicIdVal[i] is not equal to the value of SubpicIdVal[i] of the previous picture in decoding order in the same layer, the nal_unit_type for all coded slice NAL units of the subpicture in the current picture with subpicture index i shall be equal to a particular value in the range of IDR_W_RADL to CRA_NUT, inclusive.

no_pic_partition_flag equal to 1 specifies that no picture partitioning is applied to each picture referring to the PPS. no_pic_partition_flag equal to 0 specifies each picture referring to the PPS may be partitioned into more than one tile or slice.

It is a requirement of bitstream conformance that the value of no_pic_partition_flag shall be the same for all PPSs that are referred to by coded pictures within a CLVS.

It is a requirement of bitstream conformance that the value of no_pic_partition_flag shall not be equal to 1 when the value of sps_num_subpics_minus1+1 is greater than 1.

pps_log2_ctu_size_minus5 plus 5 specifies the luma coding tree block size of each CTU.

pps_log2_ctu_size_minus5 shall be equal to sps_log2_ctu_size_minus5.

num_exp_tile_columns_minus1 plus 1 specifies the number of explicitly provided tile column widths. The value of num_exp_tile_columns_minus1 shall be in the range of 0 to PicWidthInCtbsY-1, inclusive.

When no_pic_partition_flag is equal to 1, the value of num_exp_tile_columns_minus1 is inferred to be equal to 0.

num_exp_tile_rows_minus1 plus 1 specifies the number of explicitly provided tile row heights. The value of num_exp_tile_rows_minus1 shall be in the range of 0 to PicHeightInCtbsY-1, inclusive. When no_pic_partition_flag is equal to 1, the value of num_exp_tile_rows_minus1 is inferred to be equal to 0.

tile_column_width_minus1[i] plus 1 specifies the width of the i-th tile column in units of CTBs for i in the range of 0 to num_exp_tile_columns_minus1-1, inclusive.

tile_column_width_minus1[num_exp_tile_columns_minus1] is used to derive the width of the tile columns with index greater than or equal to num_exp_tile_columns_minus1 as specified in clause 6.5.1.

The value of tile_column_width_minus1 [i] shall be in the range of 0 to PicWidthInCtbsY-1, inclusive.

When not present, the value of tile_column_width_minus1[0] is inferred to be equal to PicWidthInCtbsY-1.

tile_row_height_minus1[i] plus 1 specifies the height of the i-th tile row in units of CTBs for i in the range of 0 to num_exp_tile_rows_minus1-1, inclusive. tile_row_height_minus1[num_exp_tile_rows_minus1] is used to derive the height of the tile rows with index greater than or equal to num_exp_tile_rows_minus1 as specified in clause 6.5.1. The value of tile_row_height_minus1[i] shall be in the range of 0 to PicHeightInCtbsY-1, inclusive. When not present, the value of tile_row_height_minus1[0] is inferred to be equal to PicHeightInCtbsY-1.

rect_slice_flag equal to 0 specifies that tiles within each slice are in raster scan order and the slice information is not signalled in PPS. rect_slice_flag equal to 1 specifies that tiles within each slice cover a rectangular region of the picture and the slice information is signalled in the PPS. When not present, rect_slice_flag is inferred to be equal to 1. When subpic_info_present_flag is equal to 1, the value of rect_slice_flag shall be equal to 1.

single_slice_per_subpic_flag equal to 1 specifies that each subpicture consists of one and only one rectangular slice. single_slice_per_subpic_flag equal to 0 specifies that each subpicture may consist of one or more rectangular slices. When single_slice_per_subpic_flag is equal to 1, num_slices_in_pic_minus1 is

inferred to be equal to $\text{sps_num_subpics_minus1}$. When not present, the value of

$\text{single_slice_per_subpic_flag}$ is inferred to be equal to 0.

$\text{num_slices_in_pic_minus1}$ plus 1 specifies the number of rectangular slices in each picture referring to the PPS. The value of $\text{num_slices_in_pic_minus1}$ shall be in the range of 0 to $\text{MaxSlicesPerPicture}-1$, inclusive, where $\text{MaxSlicesPerPicture}$ is specified in Annex A. When $\text{no_pic_partition_flag}$ is equal to 1, the value of $\text{num_slices_in_pic_minus1}$ is inferred to be equal to 0.

$\text{tile_idx_delta_present_flag}$ equal to 0 specifies that tile_idx_delta values are not present in the PPS and all rectangular slices in pictures referring to the PPS are specified in raster order according to the process defined in clause 6.5.1. $\text{tile_idx_delta_present_flag}$ equal to 1 specifies that tile_idx_delta values may be present in the PPS and all rectangular slices in pictures referring to the PPS are specified in the order indicated by the values of tile_idx_delta . When not present, the value of $\text{tile_idx_delta_present_flag}$ is inferred to be equal to 0.

$\text{slice_width_in_tiles_minus1}[i]$ plus 1 specifies the width of the i -th rectangular slice in units of tile columns. The value of $\text{slice_width_in_tiles_minus1}[i]$ shall be in the range of 0 to $\text{NumTileColumns}-1$, inclusive. When $\text{slice_width_in_tiles_minus1}[i]$ is not present, the following applies: If NumTileColumns is equal to 1, the value of $\text{slice_width_in_tiles_minus1}[i]$ is inferred to be equal to 0. Otherwise, the value of $\text{slice_width_in_tiles_minus1}[i]$ is inferred as specified in clause 6.5.1.

$\text{slice_height_in_tiles_minus1}[i]$ plus 1 specifies the height of the i -th rectangular slice in units of tile rows. The value of $\text{slice_height_in_tiles_minus1}[i]$ shall be in the range of 0 to $\text{NumTileRows}-1$, inclusive.

When $\text{slice_height_in_tiles_minus1}[i]$ is not present, the following applies: If NumTileRows is equal to 1, or $\text{tile_idx_delta_present_flag}$ is equal to 0 and $\text{tileIdx} \% \text{NumTileColumns}$ is greater than 0), the value of $\text{slice_height_in_tiles_minus1}[i]$ is inferred to be equal to 0. Otherwise (NumTileRows is not equal to 1, and $\text{tile_idx_delta_present_flag}$ is equal to 1 or $\text{tileIdx} \% \text{NumTileColumns}$ is equal to 0), when $\text{tile_idx_delta_present_flag}$ is equal to 1 or $\text{tileIdx} \% \text{NumTileColumns}$ is equal to 0, the value of $\text{slice_height_in_tiles_minus1}[i]$ is inferred to be equal to $\text{slice_height_in_tiles_minus1}[i]-1$.

$\text{num_exp_slices_in_tile}[i]$ specifies the number of explicitly provided slice heights in the current tile that contains more than one rectangular slices. The value of $\text{num_exp_slices_in_tile}[i]$ shall be in the range of 0 to $\text{RowHeight}[\text{tileY}]-1$, inclusive, where tileY is the tile row index containing the i -th slice. When not present, the value of $\text{num_exp_slices_in_tile}[i]$ is inferred to be equal to 0. When

$\text{num_exp_slices_in_tile}[i]$ is equal to 0, the value of the variable $\text{NumSlicesInTile}[i]$ is derived to be equal to 1.

$\text{exp_slice_height_in_ctus_minus1}[j]$ plus 1 specifies the height of the j -th rectangular slice in the current tile in units of CTU rows. The value of $\text{exp_slice_height_in_ctus_minus1}[j]$ shall be in the range of 0 to $\text{RowHeight}[\text{tileY}]-1$, inclusive, where tileY is the tile row index of the current tile.

When $\text{num_exp_slices_in_tile}[i]$ is greater than 0, the variable $\text{NumSlicesInTile}[i]$ and $\text{SliceHeightInCtusMinus1}[i+k]$ for k in the range of 0 to $\text{NumSlicesInTile}[i]-1$ are derived as follows:

(41) TABLE-US-00016 remainingHeightInCtbsY = $\text{RowHeight}[\text{SliceTopLeftTileIdx}[i] / \text{NumTileColumns}]$ numExpSliceInTile = $\text{num_exp_slices_in_tile}[i]$ for ($j = 0; j < \text{numExpSliceInTile} - 1; j++$) { $\text{SliceHeightInCtusMinus1}[j] = \text{exp_slice_height_in_ctu_minus1}[j]$ remainingHeightInCtbsY -= $\text{SliceHeightInCtusMinus1}[j]$ } uniformSliceHeightMinus1 = $\text{SliceHeightInCtusMinus1}[i - 1]$ (81) while(remainingHeightInCtbsY >= (uniformSliceHeightMinus1 + 1)) { $\text{SliceHeightInCtusMinus1}[j] = \text{uniformSliceHeightMinus1}$ remainingHeightInCtbsY -= (uniformSliceHeightMinus1 + 1) } j++ } if(remainingHeightInCtbsY > 0) { $\text{SliceHeightInCtusMinus1}[j] = \text{remainingHeightInCtbsY}$ } NumSlicesInTile[i] = j

$\text{tile_idx_delta}[i]$ specifies the difference between the tile index of the first tile in the i -th rectangular slice and the tile index of the first tile in the $(i+1)$ -th rectangular slice. The value of $\text{tile_idx_delta}[i]$ shall be in the range of $-\text{NumTilesInPic}+1$ to $\text{NumTilesInPic}-1$, inclusive. When not present, the value of $\text{tile_idx_delta}[i]$ is inferred to be equal to 0. When present, the value of $\text{tile_idx_delta}[i]$ shall not be equal to 0.

$\text{loop_filter_across_tiles_enabled_flag}$ equal to 1 specifies that in-loop filtering operations may be performed across tile boundaries in pictures referring to the PPS. $\text{loop_filter_across_tiles_enabled_flag}$ equal to 0 specifies that in-loop filtering operations are not performed across tile boundaries in pictures referring to the PPS. The in-loop filtering operations include the deblocking filter, sample adaptive offset

filter, and adaptive loop filter operations. When not present, the value of

loop_filter_across_tiles_enabled_flag is inferred to be equal to 1.

loop_filter_across_slices_enabled_flag equal to 1 specifies that in-loop filtering operations may be performed across slice boundaries in pictures referring to the PPS. loop_filter_across_slice_enabled_flag equal to 0 specifies that in-loop filtering operations are not performed across slice boundaries in pictures referring to the PPS. The in-loop filtering operations include the deblocking filter, sample adaptive offset filter, and adaptive loop filter operations. When not present, the value of loop_filter_across_slices_enabled_flag is inferred to be equal to 0.

cabac_init_present_flag equal to 1 specifies that cabac_init_flag is present in slice headers referring to the PPS. cabac_init_present_flag equal to 0 specifies that cabac_init_flag is not present in slice headers referring to the PPS.

num_ref_idx_default_active_minus1[i] plus 1, when i is equal to 0, specifies the inferred value of the variable NumRefIdxActive[0] for P or B slices with num_ref_idx_active_override_flag equal to 0, and, when i is equal to 1, specifies the inferred value of NumRefIdxActive[1] for B slices with num_ref_idx_active_override_flag equal to 0. The value of num_ref_idx_default_active_minus1[i] shall be in the range of 0 to 14, inclusive.

rpl1_idx_present_flag equal to 0 specifies that ref_pic_list_sps_flag[1] and ref_pic_list_idx[1] are not present in the PH syntax structures or the slice headers for pictures referring to the PPS.

rpl1_idx_present_flag equal to 1 specifies that ref_pic_list_sps_flag[1] and ref_pic_list_idx[1] may be present in the PH syntax structures or the slice headers for pictures referring to the PPS.

init_qp_minus26 plus 26 specifies the initial value of SliceQp.sub.Y for each slice referring to the PPS.

The initial value of SliceQp.sub.Y is modified at the picture level when a non-zero value of ph_qp_delta is decoded or at the slice level when a non-zero value of slice_qp_delta is decoded. The value of init_qp_minus26 shall be in the range of $-(26+QpBdOffset)$ to +37, inclusive.

cu_qp_delta_enabled_flag equal to 1 specifies that the ph_cu_qp_delta_subdiv_intra_slice and ph_cu_qp_delta_subdiv_inter_slice syntax elements are present in PHs referring to the PPS and cu_qp_delta_abs may be present in the transform unit syntax. cu_qp_delta_enabled_flag equal to 0 specifies that the ph_cu_qp_delta_subdiv_intra_slice and ph_cu_qp_delta_subdiv_inter_slice syntax elements are not present in PHs referring to the PPS and cu_qp_delta_abs is not present in the transform unit syntax.

pps_chroma_tool_offsets_present_flag equal to 1 specifies that chroma tool offsets related syntax elements are present in the PPS RBSP syntax structure. pps_chroma_tool_offsets_present_flag equal to 0 specifies that chroma tool offsets related syntax elements are not present in the PPS RB SP syntax structure. When ChromaArrayType is equal to 0, the value of pps_chroma_tool_offsets_present_flag shall be equal to 0.

pps_cb_qp_offset and pps_cr_qp_offset specify the offsets to the luma quantization parameter $Qp'.sub.Y$ used for deriving $Qp'.sub.Cb$ and $Qp'.sub.Cr$, respectively. The values of pps_cb_qp_offset and pps_cr_qp_offset shall be in the range of -12 to +12, inclusive. When ChromaArrayType is equal to 0, pps_cb_qp_offset and pps_cr_qp_offset are not used in the decoding process and decoders shall ignore their value. When not present, the values of pps_cb_qp_offset and pps_cr_qp_offset are inferred to be equal to 0.

pps_joint_ether_qp_offset_present_flag equal to 1 specifies that pps_joint_cbr_qp_offset_value and joint_cbr_qp_offset_list[i] are present in the PPS RBSP syntax structure.

pps_joint_cbr_qp_offset_present_flag equal to 0 specifies that pps_joint_cbr_qp_offset_value and joint_cbr_qp_offset_list[i] are not present in the PPS RBSP syntax structure. When ChromaArrayType is equal to 0 or sps_joint_cbr_enabled_flag is equal to 0, the value of

pps_joint_cbr_qp_offset_present_flag shall be equal to 0. When not present, the value of

pps_joint_cbr_qp_offset_present_flag is inferred to be equal to 0.

pps_joint_ether_qp_offset_value specifies the offset to the luma quantization parameter $Qp'y$ used for deriving $Qp'.sub.CbCr$. The value of pps_joint_cbr_qp_offset_value shall be in the range of -12 to +12, inclusive. When ChromaArrayType is equal to 0 or sps_joint_cbr_enabled_flag is equal to 0,

pps_joint_cbr_qp_offset_value is not used in the decoding process and decoders shall ignore its value.

When pps_joint_cbr_qp_offset_present_flag is equal to 0, pps_joint_cbr_qp_offset_value is not present

and is inferred to be equal to 0.

pps_slice_ehroma_qp_offsets_present_flag equal to 1 specifies that the slice_cb_qp_offset and slice_cr_qp_offset syntax elements are present in the associated slice headers.

pps_slice_chroma_qp_offsets_present_flag equal to 0 specifies that the slice_cb_qp_offset and slice_cr_qp_offset syntax elements are not present in the associated slice headers. When not present, the value of pps_slice_chroma_qp_offsets_present_flag is inferred to be equal to 0.

pps_cu_chroma_qp_offset_list_enabled_flag equal to 1 specifies that the ph_cu_chroma_qp_offset_subdiv_intra_slice and ph_cu_chroma_qp_offset_subdiv_inter_slice syntax elements are present in PHs referring to the PPS and cu_chroma_qp_offset_flag may be present in the transform unit syntax and the palette coding syntax. pps_cu_chroma_qp_offset_list_enabled_flag equal to 0 specifies that the ph_cu_chroma_qp_offset_subdiv_intra_slice and ph_cu_chroma_qp_offset_subdiv_inter_slice syntax elements are not present in PHs referring to the PPS and the cu_chroma_qp_offset_flag is not present in the transform unit syntax and the palette coding syntax. When not present, the value of pps_cu_chroma_qp_offset_list_enabled_flag is inferred to be equal to 0.

chroma_qp_offset_list_len_minus1 plus 1 specifies the number of cb_qp_offset_list[i], cr_qp_offset_list[i], and joint_cbc_r_qp_offset_list[i], syntax elements that are present in the PPS RBSP syntax structure. The value of chroma_qp_offset_list_len_minus1 shall be in the range of 0 to 5, inclusive. cb_qp_offset_list[i], cr_qp_offset_list[i], and joint_cbc_r_qp_offset_list[i], specify offsets used in the derivation of Qp'.sub.Cb, Qp'.sub.Cr, and QP'.sub.CbCr, respectively. The values of cb_qp_offset_list[i], cr_qp_offset_list[i], and joint_cbc_r_qp_offset_list[i] shall be in the range of -12 to +12, inclusive. When pps_joint_cbc_r_qp_offset_present_flag is equal to 0, joint_cbc_r_qp_offset_list[i] is not present and it is inferred to be equal to 0.

pps_weighted_pred_flag equal to 0 specifies that weighted prediction is not applied to P slices referring to the PPS. pps_weighted_pred_flag equal to 1 specifies that weighted prediction is applied to P slices referring to the PPS. When sps_weighted_pred_flag is equal to 0, the value of pps_weighted_pred_flag shall be equal to 0.

pps_weighted_bipred_flag equal to 0 specifies that explicit weighted prediction is not applied to B slices referring to the PPS. pps_weighted_bipred_flag equal to 1 specifies that explicit weighted prediction is applied to B slices referring to the PPS. When sps_weighted_bipred_flag is equal to 0, the value of pps_weighted_bipred_flag shall be equal to 0.

deblocking_filter_control_present_flag equal to 1 specifies the presence of deblocking filter control syntax elements in the PPS. deblocking_filter_control_present_flag equal to 0 specifies the absence of deblocking filter control syntax elements in the PPS.

deblocking_filter_override_enabled_flag equal to 1 specifies the presence of ph_deblocking_filter_override_flag in the PHs referring to the PPS or slice_deblocking_filter_override_flag in the slice headers referring to the PPS.

deblocking_filter_override_enabled_flag equal to 0 specifies the absence of ph_deblocking_filter_override_flag in PHs referring to the PPS or slice_deblocking_filter_override_flag in slice headers referring to the PPS. When not present, the value of deblocking_filter_override_enabled_flag is inferred to be equal to 0.

pps_deblocking_filter_disabled_flag equal to 1 specifies that the operation of deblocking filter is not applied for slices referring to the PPS in which slice_deblocking_filter_disabled_flag is not present.

pps_deblocking_filter_disabled_flag equal to 0 specifies that the operation of the deblocking filter is applied for slices referring to the PPS in which slice_deblocking_filter_disabled_flag is not present. When not present, the value of pps_deblocking_filter_disabled_flag is inferred to be equal to 0.

pps_beta_offset_div2 and pps_tc_offset_div2 specify the default deblocking parameter offsets for β and tC (divided by 2) that are applied to the luma component for slices referring to the PPS, unless the default deblocking parameter offsets are overridden by the deblocking parameter offsets present in the picture headers or the slice headers of the slices referring to the PPS. The values of pps_beta_offset_div2 and pps_tc_offset_div2 shall both be in the range of -12 to 12, inclusive. When not present, the values of pps_beta_offset_div2 and pps_tc_offset_div2 are both inferred to be equal to 0.

pps_cb_beta_offset_div2 and pps_cb_tc_offset_div2 specify the default deblocking parameter offsets for

and tC (divided by 2) that are applied to the Cb component for slices referring to the PPS, unless the default deblocking parameter offsets are overridden by the deblocking parameter offsets present in the picture headers or the slice headers of the slices referring to the PPS. The values of pps_cb_beta_offset_div2 and pps_cb_tc_offset_div2 shall both be in the range of -12 to 12 , inclusive. When not present, the values of pps_cb_beta_offset_div2 and pps_cb_tc_offset_div2 are both inferred to be equal to 0.

pps_cr_beta_offset_div2 and pps_cr_tc_offset_div2 specify the default deblocking parameter offsets for and tC (divided by 2) that are applied to the Cr component for slices referring to the PPS, unless the default deblocking parameter offsets are overridden by the deblocking parameter offsets present in the picture headers or the slice headers of the slices referring to the PPS. The values of pps_cr_beta_offset_div2 and pps_cr_tc_offset_div2 shall both be in the range of -12 to 12 , inclusive. When not present, the values of pps_cr_beta_offset_div2 and pps_cric_offset_div2 are both inferred to be equal to 0.

rpl_info_in_ph_flag equal to 1 specifies that reference picture list information is present in the PH syntax structure and not present in slice headers referring to the PPS that do not contain a PH syntax structure. rpl_info_in_ph_flag equal to 0 specifies that reference picture list information is not present in the PH syntax structure and may be present in slice headers referring to the PPS that do not contain a PH syntax structure.

dbf_info_in_ph_flag equal to 1 specifies that deblocking filter information is present in the PH syntax structure and not present in slice headers referring to the PPS that do not contain a PH syntax structure. dbf_info_in_ph_flag equal to 0 specifies that deblocking filter information is not present in the PH syntax structure and may be present in slice headers referring to the PPS that do not contain a PH syntax structure. When not present, the value of dbf_info_in_ph_flag is inferred to be equal to 0.

sao_info_in_ph_flag equal to 1 specifies that SAO filter information is present in the PH syntax structure and not present in slice headers referring to the PPS that do not contain a PH syntax structure.

sao_info_in_ph_flag equal to 0 specifies that SAO filter information is not present in the PH syntax structure and may be present in slice headers referring to the PPS that do not contain a PH syntax structure.

alf_info_in_ph_flag equal to 1 specifies that ALF information is present in the PH syntax structure and not present in slice headers referring to the PPS that do not contain a PH syntax structure. alf_info_in_ph_flag equal to 0 specifies that ALF information is not present in the PH syntax structure and may be present in slice headers referring to the PPS that do not contain a PH syntax structure.

wp_info_in_ph_flag equal to 1 specifies that weighted prediction information may be present in the PH syntax structure and not present in slice headers referring to the PPS that do not contain a PH syntax structure. wp_info_in_ph_flag equal to 0 specifies that weighted prediction information is not present in the PH syntax structure and may be present in slice headers referring to the PPS that do not contain a PH syntax structure. When not present, the value of wp_info_in_ph_flag is inferred to be equal to 0.

qp_delta_info_in_ph_flag equal to 1 specifies that QP delta information is present in the PH syntax structure and not present in slice headers referring to the PPS that do not contain a PH syntax structure. qp_delta_info_in_ph_flag equal to 0 specifies that QP delta information is not present in the PH syntax structure and may be present in slice headers referring to the PPS that do not contain a PH syntax structure.

pps_ref_wraparound_enabled_flag equal to 1 specifies that horizontal wrap-around motion compensation is applied in inter prediction. pps_ref_wraparound_enabled_flag equal to 0 specifies that horizontal wrap-around motion compensation is not applied. When the value of $\text{CtbSizeY}/\text{MinCbSizeY}+1$ is greater than $\text{pic_width_in_luma_samples}/\text{MinCbSizeY}-1$, the value of pps_ref_wraparound_enabled_flag shall be equal to 0. When pps_ref_wraparound_enabled_flag is equal to 0, the value of pps_ref_wraparound_enabled_flag shall be equal to 0.

pps_ref_wraparound_offset plus $(\text{CtbSizeY}/\text{MinCbSizeY})+2$ specifies the offset used for computing the horizontal wrap-around position in units of MinCbSizeY luma samples. The value of pps_ref_wraparound_offset shall be in the range of 0 to $(\text{pic_width_in_luma_samples}/\text{MinCbSizeY})-(\text{CtbSizeY}/\text{MinCbSizeY})-2$, inclusive. The variable PpsRefWraparoundOffset is set equal to $\text{pps_ref_wraparound_offset}+(\text{CtbSizeY}/\text{MinCbSizeY})+2$.

picture_header_extension_present_flag equal to 0 specifies that no PH extension syntax elements are present in PHs referring to the PPS. picture_header_extension_present_flag equal to 1 specifies that PH extension syntax elements are present in PHs referring to the PPS. picture_header_extension_present_flag shall be equal to 0 in bitstreams conforming to this version of this Specification.

slice_header_extension_present_flag equal to 0 specifies that no slice header extension syntax elements are present in the slice headers for coded pictures referring to the PPS.

slice_header_extension_present_flag equal to 1 specifies that slice header extension syntax elements are present in the slice headers for coded pictures referring to the PPS. slice_header_extension_present_flag shall be equal to 0 in bitstreams conforming to this version of this Specification.

pps_extension_flag equal to 0 specifies that no pps_extension_data_flag syntax elements are present in the PPS RBSP syntax structure. pps_extension_flag equal to 1 specifies that there are pps_extension_data_flag syntax elements present in the PPS RBSP syntax structure.

pps_extension_data_flag may have any value. Its presence and value do not affect decoder conformance to profiles specified in this version of this Specification. Decoders conforming to this version of this Specification shall ignore all pps_extension_data_flag syntax elements.

3.7. APS Syntax and Semantics

In the latest VVC draft text, the APS syntax and semantics are as follows:

(42) TABLE-US-00017 Descriptor adaptation_parameter_set_rbsp() { **adaptation**_parameter_set_id u(5) **aps**_params_type u(3) if(aps_params_type == ALF_APS) **alf_data**() else if(aps_params_type == LMCS_APS) **lmcs_data**() else if(aps_params_type == SCALING_APS) **scaling_list_data**() **aps**_extension_flag u(1) if(aps_extension_flag) while(more_rbsp_data()) **aps**_extension_data_flag u(1) rbsp_trailing_bits() }

The APS RBSP contains a ALF syntax structure, i.e., **alf_data**().

(43) TABLE-US-00018 Descriptor **alf_data**() { **alf**_luma_filter_signal_flag u(1) **alf**_chroma_filter_signal_flag u(1) **alf**_cc_cb_filter_signal_flag u(1) **alf**_cc_cr_filter_signal_flag u(1) if(**alf**_luma_filter_signal_flag) { **alf**_luma_clip_flag u(1) **alf**_luma_num_filters_signalled_minus1 ue(v) if(**alf**_luma_num_filters_signalled_minus1 > 0) for(filtIdx = 0; filtIdx < NumAlfFilters; filtIdx++) **alf**_luma_coeff_delta_idx[filtIdx] u(v) for(sfIdx = 0; sfIdx <= **alf**_luma_num_filters_signalled_minus1; sfIdx++) for(j = 0; j < 12; j++) { **alf**_luma_coeff_abs[sfIdx][j] ue(v) if(**alf**_luma_coeff_abs[sfIdx][j]) **alf**_luma_coeff_sign[sfIdx][j] u(1) } if(**alf**_luma_clip_flag) for(sfIdx = 0; sfIdx <= **alf**_luma_num_filters_signalled_minus1; sfIdx++) for(j = 0; j < 12; j++) **alf**_luma_clip_idx[sfIdx][j] u(2) } if(**alf**_chroma_filter_signal_flag) { **alf**_chroma_clip_flag u(1) **alf**_chroma_num_alt_filters_minus1 ue(v) for(altIdx = 0; altIdx <= **alf**_chroma_num_alt_filters_minus1; altIdx++) { for(j = 0; j < 6; j++) { **alf**_chroma_coeff_abs[altIdx][j] ue(v) if(**alf**_chroma_coeff_abs[altIdx][j] > 0) **alf**_chroma_coeff_sign[altIdx][j] u(1) } if(**alf**_chroma_clip_flag) for(j = 0; j < 6; j++) **alf**_chroma_clip_idx[altIdx][j] u(2) } } if(**alf**_cc_cb_filter_signal_flag) { **alf**_cc_cb_filters_signalled_minus1 ue(v) for(k = 0; k < **alf**_cc_cb_filters_signalled_minus1 + 1; k++) { for(j = 0; j < 7; j++) { **alf**_cc_cb_mapped_coeff_abs[k][j] u(3) if(**alf**_cc_cb_mapped_coeff_abs[k][j]) **alf**_cc_cb_coeff_sign[k][j] u(1) } } } if(**alf**_cc_cr_filter_signal_flag) { **alf**_cc_cr_filters_signalled_minus1 ue(v) for(k = 0; k < **alf**_cc_cr_filters_signalled_minus1 + 1; k++) { for(j = 0; j < 7; j++) { **alf**_cc_cr_mapped_coeff_abs[k][j] u(3) if(**alf**_cc_cr_mapped_coeff_abs[k][j]) **alf**_cc_cr_coeff_sign[k][j] u(1) } } } } }

The APS RBSP contains a LMCS syntax structure, i.e., **lmcs_data**().

(44) TABLE-US-00019 Descriptor **lmcs_data**() { **lmcs**_min_bin_idx ue(v) **lmcs**_delta_max_bin_idx ue(v) **lmcs**_delta_cw_prec_minus1 ue(v) for(i = **lmcs**_min_bin_idx; i <= **lmcs**_max_bin_idx; i++) { **lmcs**_delta_abs_cw[i] u(v) if(**lmcs**_delta_abs_cw[i] > 0) **lmcs**_delta_sign_cw_flag[i] u(1) } **lmcs**_delta_abs_crs u(3) if(**lmcs**_delta_abs_crs > 0) **lmcs**_delta_sign_crs_flag u(1) }

The APS RBSP contains a scaling list data syntax structure, i.e., **scaling_list_data**().

(45) TABLE-US-00020 Descriptor **scaling_list_data**() { **scaling**_matrix_for_lfnst_disabled_flag u(1)

```

scaling_list_chroma_present_flag u(1)      for( id = 0; id < 28; id ++ )      matrixSize = (id < 2) ? 2 : ((
id < 8) ? 4 : 8)      if( scaling_list_chroma_present_flag ||      ( id % 3 == 2 ) || ( id == 27 ) ) {
    scaling_list_copy_mode_flag[ id ] u(1)      if( !scaling_list_copy_mode_flag[ id ] )
scaling_list_pred_mode_flag[ id ] u(1)      if( ( scaling_list_copy_mode_flag[ id ] ||
scaling_list_pred_mode_flag[ id ] ) &&      id != 0 && id != 2 && id != 8 )
scaling_list_pred_id_delta[ id ] ue(v)      if( !scaling_list_copy_mode_flag[ id ] ) {      nextCoef
= 0      if( id > 13 ) {      scaling_list_dc_coef[ id - 14 ] se(v)      nextCoef +=
scaling_list_dc_coef[ id - 14 ]      }      for( i = 0; i < matrixSize * matrixSize; i++ ) {
        x = DiagScanOrder[ 3 ][ 3 ][ i ][ 0 ]      y = DiagScanOrder[ 3 ][ 3 ][ i ][ 1 ]
        if( !( id > 25 && x >= 4 && y >= 4 ) ) {      scaling_list_delta_coef[ id ][ i ] se(v)
            nextCoef += scaling_list_delta_coef[ id ][ i ]      }      ScalingList[ id ][ i
] = nextCoef      }      }      }      } }

```

Each APS RBSP shall be available to the decoding process prior to it being referenced, included in at least one AU with TemporalId less than or equal to the TemporalId of the coded slice NAL unit that refers it or provided through external means.

All APS NAL units with a particular value of **adaptation_parameter_set_id** and a particular value of **aps_params_type** within a PU, regardless of whether they are prefix or suffix APS NAL units, shall have the same content.

adaptation_parameter_set_id provides an identifier for the APS for reference by other syntax elements.

When **aps_params_type** is equal to ALF_APS or SCALING_APS, the value of **adaptation_parameter_set_id** shall be in the range of 0 to 7, inclusive.

When **aps_params_type** is equal to LMCS_APS, the value of **adaptation_parameter_set_id** shall be in the range of 0 to 3, inclusive.

Let **apsLayerId** be the value of the **nuh_layer_id** of a particular APS NAL unit, and **vclLayerId** be the value of the **nuh_layer_id** of a particular VCL NAL unit. The particular VCL NAL unit shall not refer to the particular APS NAL unit unless **apsLayerId** is less than or equal to **vclLayerId** and the layer with **nuh_layer_id** equal to **apsLayerId** is included in at least one OLS that includes the layer with **nuh_layer_id** equal to **vclLayerId**.

aps_params_type specifies the type of APS parameters carried in the APS as specified in Table 6.

(46) TABLE-US-00021 TABLE 6 APS parameters type codes and types of APS parameters

Name of aps_params_type	aps_params_type	Type of APS parameters
0	ALF_APS	ALF parameters
1	LMCS_APS	LMCS parameters
2	SCALING_APS	Scaling list parameters
3 . . . 7	Reserved	Reserved

All APS NAL units with a particular value of **aps_params_type**, regardless of the **nuh_layer_id** values, share the same value space for **adaptation_parameter_set_id**. APS NAL units with different values of **aps_params_type** use separate values spaces for **adaptation_parameter_set_id**. NOTE 1—An APS NAL unit (with a particular value of **adaptation_parameter_set_id** and a particular value of **aps_params_type**) can be shared across pictures, and different slices within a picture can refer to different ALF APSs. NOTE 2—A suffix APS NAL unit associated with a particular VCL NAL unit (this VCL NAL unit precedes the suffix APS NAL unit in decoding order) is not for use by the particular VCL NAL unit, but for use by VCL NAL units following the suffix APS NAL unit in decoding order.

aps_extension_flag equal to 0 specifies that no **aps_extension_data_flag** syntax elements are present in the APS RBSP syntax structure. **aps_extension_flag** equal to 1 specifies that there are **aps_extension_data_flag** syntax elements present in the APS RBSP syntax structure.

aps_extension_data_flag may have any value. Its presence and value do not affect decoder conformance to profiles specified in this version of this Specification. Decoders conforming to this version of this Specification shall ignore all **aps_extension_data_flag** syntax elements.

alf_lumailter_signal_flag equal to 1 specifies that a luma filter set is signalled.

alf_luma_filter_signal_flag equal to 0 specifies that a luma filter set is not signalled.

alf_chromailter_signal_flag equal to 1 specifies that a chroma filter is signalled.

alf_chroma_filter_signal_flag equal to 0 specifies that a chroma filter is not signalled. When **ChromaArrayType** is equal to 0, **alf_chroma_filter_signal_flag** shall be equal to 0.

At least one of the values of **alf_luma_filter_signal_flag**, **alf_chroma_filter_signal_flag**, **alf_cc_cb_filter_signal_flag** and **alf_cc_cr_filter_signal_flag** shall be equal to 1.

The variable NumAlfFilters specifying the number of different adaptive loop filters is set equal to 25. alf_luma_clip_flag equal to 0 specifies that linear adaptive loop filtering is applied on luma component. alf_luma_clip_flag equal to 1 specifies that non-linear adaptive loop filtering may be applied on luma component.

alf_luma_num_filters_signalled_minus1 plus 1 specifies the number of adaptive loop filter classes for which luma coefficients can be signalled. The value of alf_luma_num_filters_signalled_minus1 shall be in the range of 0 to NumAlfFilters-1, inclusive.

alf_luma_coeff_delta_idx[filtIdx] specifies the indices of the signalled adaptive loop filter luma coefficient deltas for the filter class indicated by filtIdx ranging from 0 to NumAlfFilters-1. When alf_luma_coeff_delta_idx[filtIdx] is not present, it is inferred to be equal to 0. The length of alf_luma_coeff_delta_idx[filtIdx] is Ceil(Log2(alf_luma_num_filters_signalled_minus1+1)) bits. The value of alf_luma_coeff_delta_idx[filtIdx] shall be in the range of 0 to

alf_luma_num_filters_signalled_minus1, inclusive.

alf_luma_coeff_abs[sfIdx][j] specifies the absolute value of the j-th coefficient of the signalled luma filter indicated by sfIdx. When alf_luma_coeff_abs[sfIdx][j] is not present, it is inferred to be equal 0. The value of alf_luma_coeff_abs[sfIdx][j] shall be in the range of 0 to 128, inclusive.

alf_luma_coeff_sign[sfIdx][j] specifies the sign of the j-th luma coefficient of the filter indicated by sfIdx as follows: If alf_luma_coeff_sign[sfIdx][j] is equal to 0, the corresponding luma filter coefficient has a positive value. Otherwise (alf_luma_coeff_sign[sfIdx][j] is equal to 1), the corresponding luma filter coefficient has a negative value.

When alf_luma_coeff_sign[sfIdx][j] is not present, it is inferred to be equal to 0.

The variable filtCoeff[sfIdx][j] with sfIdx=0...alf_luma_num_filters_signalled_minus1, j=0...11 is initialized as follows:

(47) TABLE-US-00022 $\text{filtCoeff}[\text{sfIdx}][j] = \text{alf_luma_coeff_abs}[\text{sfIdx}][j] * (93) (1 - 2 * \text{alf_luma_coeff_sign}[\text{sfIdx}][j])$

The luma filter coefficients AlfCoeff.sub.L[adaptation_parameter_set_id] with elements

AlfCoeff.sub.L[adaptation_parameter_set_id][filtIdx][j], with filtIdx=0...NumAlfFilters-1 and j=0...11 are derived as follows:

$\text{AlfCoeff.sub.L[adaptation_parameter_set_id][filtIdx][j]} = \text{filtCoeff}[\text{alf_luma_coeff_delta_idx}[\text{filtIdx}]] [j]$ (94)

The fixed filter coefficients AlfFixFiltCoeff[i][j] with i=0...64, j=0...11 and the class to filter mapping AlfClassToFiltMap[m][n] with m=0...15 and n=0...24 are derived as follows:

(48) TABLE-US-00023 AlfFixFiltCoeff = (95) { { 0, 0, 2, -3, 1, -4, 1, 7, -1, 1, -1, 5 } { 0, 0, 0, 0, 0, -1, 0, 1, 0, 0, -1, 2 } { 0, 0, 0, 0, 0, 0, 0, 0, 1, 0, 0, 0 } { 0, 0, 0, 0, 0, 0, 0, 0, 0, 0, -1, 1 } { 2, 2, -7, -3, 0, -5, 13, 22, 12, -3, -3, 17 } { -1, 0, 6, -8, 1, -5, 1, 23, 0, 2, -5, 10 } { 0, 0, -1, -1, 0, -1, 2, 1, 0, 0, -1, 4 } { 0, 0, 3, -11, 1, 0, -1, 35, 5, 2, -9, 9 } { 0, 0, 8, -8, -2, -7, 4, 4, 2, 1, -1, 25 } { 0, 0, 1, -1, 0, -3, 1, 3, -1, 1, -1, 3 } { 0, 0, 3, -3, 0, -6, 5, -1, 2, 1, -4, 21 } { -7, 1, 5, 4, -3, 5, 11, 13, 12, -8, 11, 12 } { -5, -3, 6, -2, -3, 8, 14, 15, 2, -7, 11, 16 } { 2, -1, -6, -5, -2, -2, 20, 14, -4, 0, -3, 25 } { 3, 1, -8, -4, 0, -8, 22, 5, -3, 2, -10, 29 } { 2, 1, -7, -1, 2, -11, 23, -5, 0, 2, -10, 29 } { -6, -3, 8, 9, -4, 8, 9, 7, 14, -2, 8, 9 } { 2, 1, -4, -7, 0, -8, 17, 22, 1, -1, -4, 23 } { 3, 0, -5, -7, 0, -7, 15, 18, -5, 0, -5, 27 } { 2, 0, 0, -7, 1, -10, 13, 13, -4, 2, -7, 24 } { 3, 3, -13, 4, -2, -5, 9, 21, 25, -2, -3, 12 } { -5, -2, 7, -3, -7, 9, 8, 9, 16, -2, 15, 12 } { 0, -1, 0, -7, -5, 4, 11, 11, 8, -6, 12, 21 } { 3, -2, -3, -8, -4, -1, 16, 15, -2, -3, 3, 26 } { 2, 1, -5, -4, -1, -8, 16, 4, -2, 1, -7, 33 } { 2, 1, -4, -2, 1, -10, 17, -2, 0, 2, -11, 33 } { 1, -2, 7, -15, -16, 10, 8, 8, 20, 11, 14, 11 } { 2, 2, 3, -13, -13, 4, 8, 12, 2, -3, 16, 24 } { 1, 4, 0, -7, -8, -4, 9, 9, -2, -2, 8, 29 } { 1, 1, 2, -4, -1, -6, 6, 3, -1, -1, -3, 30 } { -7, 3, 2, 10, -2, 3, 7, 11, 19, -7, 8, 10 } { 0, -2, -5, -3, -2, 4, 20, 15, -1, -3, -1, 22 } { 3, -1, -8, -4, -1, -4, 22, 8, -4, 2, -8, 28 } { 0, 3, -14, 3, 0, 1, 19, 17, 8, -3, -7, 20 } { 0, 2, -1, -8, 3, -6, 5, 21, 1, 1, -9, 13 } { -4, -2, 8, 20, -2, 2, 3, 5, 21, 4, 6, 1 } { 2, -2, -3, -9, -4, 2, 14, 16, 3, -6, 8, 24 } { 2, 1, 5, -16, -7, 2, 3, 11, 15, -3, 11, 22 } { 1, 2, 3, -11, -2, -5, 4, 8, 9, -3, -2, 26 } { 0, -1, 10, -9, -1, -8, 2, 3, 4, 0, 0, 29 } { 1, 2, 0, -5, 1, -9, 9, 3, 0, 1, -7, 20 } { -2, 8, -6, -4, 3, -9, -8, 45, 14, 2, -13, 7 } { 1, -1, 16, -19, -8, -4, -3, 2, 19, 0, 4, 30 } { 1, 1, -3, 0, 2, -11, 15, -5, 1, 2, -9, 24 } { 0, 1, -2, 0, 1, -4, 4, 0, 0, 1, -4, 7 } { 0, 1, 2, -5, 1, -6, 4, 10, -2, 1, -4, 10 } { 3, 0, -3, -6, -2, -6, 14, 8, -1,

-1, -3, 31} { 0, 1, 0, -2, 1, -6, 5, 1, 0, 1, -5, 13} { 3, 1, 9, -19, -21, 9, 7, 6, 13, 5, 15, 21}
 { 2, 4, 3, -12, -13, 1, 7, 8, 3, 0, 12, 26} { 3, 1, -8, -2, 0, -6, 18, 2, -2, 3, -10, 23} { 1, 1, -4,
 -1, 1, -5, 8, 1, -1, 2, -5, 10} { 0, 1, -1, 0, 0, -2, 2, 0, 0, 1, -2, 3} { 1, 1, -2, -7, 1, -7, 14, 18,
 0, 0, -7, 21} { 0, 1, 0, -2, 0, -7, 8, 1, -2, 0, -3, 24} { 0, 1, 1, -2, 2, -10, 10, 0, -2, 1, -7, 23}
 { 0, 2, 2, -11, 2, -4, -3, 39, 7, 1, -10, 9} { 1, 0, 13, -16, -5, -6, -1, 8, 6, 0, 6, 29} { 1, 3,
 1, -6, -4, -7, 9, 6, -3, -2, 3, 33} { 4, 0, -17, -1, -1, 5, 26, 8, -2, 3, -15, 30} { 0, 1, -2, 0, 2,
 -8, 12, -6, 1, 1, -6, 16} { 0, 0, 0, -1, 1, -4, 4, 0, 0, 0, -3, 11} { 0, 1, 2, -8, 2, -6, 5, 15, 0, 2, -7,
 9} { 1, -1, 12, -15, -7, -2, 3, 6, 6, -1, 7, 30} }, AlfClassToFiltMap = (96) { { 8, 2, 2, 2, 3,
 4, 53, 9, 9, 52, 4, 4, 5, 9, 2, 8, 10, 9, 1, 3, 39, 39, 10, 9, 52 } { 11, 12, 13, 14, 15, 30, 11, 17, 18,
 19, 16, 20, 20, 4, 53, 21, 22, 23, 14, 25, 26, 26, 27, 28, 10 } { 16, 12, 31, 32, 14, 16, 30, 33, 53,
 34, 35, 16, 20, 4, 7, 16, 21, 36, 18, 19, 21, 26, 37, 38, 39 } { 35, 11, 13, 14, 43, 35, 16, 4, 34, 62,
 35, 35, 30, 56, 7, 35, 21, 38, 24, 40, 16, 21, 48, 57, 39 } { 11, 31, 32, 43, 44, 16, 4, 17, 34, 45,
 30, 20, 20, 7, 5, 21, 22, 46, 40, 47, 26, 48, 63, 58, 10 } { 12, 13, 50, 51, 52, 11, 17, 53, 45, 9, 30,
 4, 53, 19, 0, 22, 23, 25, 43, 44, 37, 27, 28, 10, 55 } { 30, 33, 62, 51, 44, 20, 41, 56, 34, 45, 20,
 41, 41, 56, 5, 30, 56, 38, 40, 47, 11, 37, 42, 57, 8 } { 35, 11, 23, 32, 14, 35, 20, 4, 17, 18, 21, 20,
 20, 20, 4, 16, 21, 36, 46, 25, 41, 26, 48, 49, 58 } { 12, 31, 59, 59, 3, 33, 33, 59, 59, 52, 4, 33, 17,
 59, 55, 22, 36, 59, 259, 60, 22, 36, 59, 5, 55 } { 31, 25, 15, 60, 60, 22, 17, 19, 55, 55, 20, 20, 53,
 19, 55, 22, 46, 25, 43, 60, 37, 28, 10, 55, 52 } { 12, 31, 32, 50, 51, 11, 33, 53, 19, 45, 16, 4, 4,
 53, 5, 22, 36, 18, 25, 43, 26, 27, 27, 28, 10 } { 5, 2, 44, 52, 3, 4, 53, 45, 9, 3, 4, 56, 5, 0, 2, 5, 10,
 47, 52, 3, 63, 39, 10, 9, 52 } { 12, 34, 44, 44, 3, 56, 56, 62, 45, 9, 56, 56, 7, 5, 0, 22, 38, 40, 47,
 52, 48, 57, 39, 10, 9 } { 35, 11, 23, 14, 51, 35, 20, 41, 56, 62, 16, 20, 41, 56, 7, 16, 21, 38,
 24, 40, 26, 26, 42, 57, 39 } { 33, 34, 51, 51, 52, 41, 41, 34, 62, 0, 41, 41, 56, 7, 5, 56, 38, 38, 40,
 44, 37, 42, 57, 39, 10 } { 16, 31, 32, 15, 60, 30, 4, 17, 19, 25, 22, 20, 4, 53, 19, 21, 22, 46, 25,
 55, 26, 48, 63, 58, 55 } },

It is a requirement of bitstream conformance that the values of

AlfCoeff.sub.L[adaptation_parameter_set_id][filtIdx][j] with filtIdx=0 . . . NumAlfFilters-1, j=0 . . . 11 shall be in the range of $-2^{\text{sup.7}}$ to $2^{\text{sup.7}}-1$, inclusive.

alf_luma_clip_idx[sfIdx][j] specifies the clipping index of the clipping value to use before multiplying by the j-th coefficient of the signalled luma filter indicated by sfIdx. It is a requirement of bitstream conformance that the values of alf_luma_clip_idx[sfIdx][j] with sfIdx=0 . . .

alf_luma_num_filters_signalled_minus1 and j=0 . . . 11 shall be in the range of 0 to 3, inclusive.

The luma filter clipping values AlfClip.sub.L[adaptation_parameter_set_id] with elements

AlfClip.sub.L[adaptation_parameter_set_id][filtIdx][j], with filtIdx=0 . . . NumAlfFilters-1 and j=0 . . . 11 are derived as specified in Table 8 depending on BitDepth and clipIdx set equal to

alf_luma_clip_idx[alf_luma_coeff_delta_idx[filtIdx]][j].

alf_chroma_clip_flag equal to 0 specifies that linear adaptive loop filtering is applied on chroma components; alf_chroma_clip_flag equal to 1 specifies that non-linear adaptive loop filtering is applied on chroma components. When not present, alf_chroma_clip_flag is inferred to be equal to 0.

alf_chroma_num_alt_filters_minus1 plus 1 specifies the number of alternative filters for chroma components. The value of alf_chroma_num_alt_filters_minus1 shall be in the range of 0 to 7, inclusive.

alf_chroma_coeff_abs[altIdx][j] specifies the absolute value of the j-th chroma filter coefficient for the alternative chroma filter with index altIdx. When alf_chroma_coeff_abs[altIdx][j] is not present, it is inferred to be equal 0. The value of alf_chroma_coeff_abs[sfIdx][j] shall be in the range of 0 to 128, inclusive.

alf_chroma_coeff_sign[altIdx][j] specifies the sign of the j-th chroma filter coefficient for the alternative chroma filter with index altIdx as follows: If alf_chroma_coeff_sign[altIdx][j] is equal to 0, the corresponding chroma filter coefficient has a positive value. Otherwise (alf_chroma_coeff_sign[altIdx][j] is equal to 1), the corresponding chroma filter coefficient has a negative value.

When alf_chroma_coeff_sign[altIdx][j] is not present, it is inferred to be equal to 0.

The chroma filter coefficients AlfCoeff.sub.C[adaptation_parameter_set_id][altIdx] with elements

AlfCoeff.sub.C[adaptation_parameter_set_id][altIdx][j], with altIdx=0 . . .

alf_chroma_num_alt_filters_minus1, j=0 . . . 5 are derived as follows:

AlfCoeff.sub.C[adaptation_parameter_set_id][altIdx][j]=alf_chroma_coeff_abs[altIdx][j]*

($1-2 \cdot \text{alf_chroma_coeff_sign}[\text{altIdx}][j]$) (97)

It is a requirement of bitstream conformance that the values of

$\text{AlfCoeff.sub.C}[\text{adaptation_parameter_set_id}][\text{altIdx}][j]$ with $\text{altIdx}=0 \dots$

$\text{alf_chroma_num_alt_filters_minus1}$, $j=0 \dots 5$ shall be in the range of $-2^{\text{sup.7}}$ to $2^{\text{sup.7}}-1$, inclusive.

$\text{alf_cc_cb_filter_signal_flag}$ equal to 1 specifies that cross-component filters for the Cb color component are signalled. $\text{alf_cc_cb_filter_signal_flag}$ equal to 0 specifies that cross-component filters for Cb color component are not signalled. When ChromaArrayType is equal to 0, $\text{alf_cc_cb_filter_signal_flag}$ shall be equal to 0.

$\text{alf_cc_cb_filters_signalled_minus1}$ plus 1 specifies the number of cross-component filters for the Cb color component signalled in the current ALF APS. The value of $\text{alf_cc_cb_filters_signalled_minus1}$ shall be in the range of 0 to 3, inclusive.

$\text{alf_cc_cb_mapped_coeff_abs}[k][j]$ specifies the absolute value of the j -th mapped coefficient of the signalled k -th cross-component filter for the Cb color component. When $\text{alf_cc_cb_mapped_coeff_abs}[k][j]$ is not present, it is inferred to be equal to 0.

$\text{alf_cc_cb_coeff_sign}[k][j]$ specifies the sign of the j -th coefficient of the signalled k -th cross-component filter for the Cb color component as follows: If $\text{alf_cc_cb_coeff_sign}[k][j]$ is equal to 0, the corresponding cross-component filter coefficient has a positive value. Otherwise ($\text{alf_cc_cb_coeff_sign}[k][j]$ is equal to 1), the corresponding cross-component filter coefficient has a negative value.

When $\text{alf_cc_cb_coeff_sign}[k][j]$ is not present, it is inferred to be equal to 0.

The signalled k -th cross-component filter coefficients for the Cb color component

$\text{CcAlfApsCoeff.sub.Cb}[\text{adaptation_parameter_set_id}][k][j]$, with $j=0 \dots 6$ are derived as follows: If

$\text{alf_cc_cb_mapped_coeff_abs}[k][j]$ is equal to 0, $\text{CcAlfApsCoeff.sub.Cb}[\text{adaptation_parameter_set_id}][k][j]$ is set equal to 0. Otherwise, $\text{CcAlfApsCoeff.sub.Cb}[\text{adaptation_parameter_set_id}][k][j]$ is set equal to $(1-2 \cdot \text{alf_cc_cb_coeff_sign}[k][j]) \cdot 2^{\text{sup.alf_cc_cb_mapped_coeff_abs}[k][j]}-1$.

$\text{alf_cc_cr_filter_signal_flag}$ equal to 1 specifies that cross-component filters for the Cr color component are signalled. $\text{alf_cc_cr_filter_signal_flag}$ equal to 0 specifies that cross-component filters for the Cr color component are not signalled. When ChromaArrayType is equal to 0, $\text{alf_cc_cr_filter_signal_flag}$ shall be equal to 0.

$\text{alf_cc_cr_filters_signalled_minus1}$ plus 1 specifies the number of cross-component filters for the Cr color component signalled in the current ALF APS. The value of $\text{alf_cc_cr_filters_signalled_minus1}$ shall be in the range of 0 to 3, inclusive.

$\text{alf_cc_cr_mapped_coeff_abs}[k][j]$ specifies the absolute value of the j -th mapped coefficient of the signalled k -th cross-component filter for the Cr color component. When $\text{alf_cc_cr_mapped_coeff_abs}[k][j]$ is not present, it is inferred to be equal to 0.

$\text{alf_cc_cr_coeff_sign}[k][j]$ specifies the sign of the j -th coefficient of the signalled k -th cross-component filter for the Cr color component as follows: If $\text{alf_cc_cr_coeff_sign}[k][j]$ is equal to 0, the corresponding cross-component filter coefficient has a positive value. Otherwise ($\text{alf_cc_cr_coeff_sign}[k][j]$ is equal to 1), the corresponding cross-component filter coefficient has a negative value.

When $\text{alf_cc_cr_coeff_sign}[k][j]$ is not present, it is inferred to be equal to 0.

The signalled k -th cross-component filter coefficients for the Cr color component

$\text{CcAlfApsCoeff.sub.Cr}[\text{adaptation_parameter_set_id}][k][j]$, with $j=0 \dots 6$ are derived as follows: If

$\text{alf_cc_cr_mapped_coeff_abs}[k][j]$ is equal to 0, $\text{CcAlfApsCoeff.sub.Cr}[\text{adaptation_parameter_set_id}][k][j]$ is set equal to 0. Otherwise, $\text{CcAlfApsCoeff.sub.Cr}[\text{adaptation_parameter_set_id}][k][j]$ is set equal to $(1-2 \cdot \text{alf_cc_cr_coeff_sign}[k][j]) \cdot 2^{\text{sup.alf_cc_cr_mapped_coeff_abs}[k][j]}-1$.

$\text{alf_chroma_clip_idx}[\text{altIdx}][j]$ specifies the clipping index of the clipping value to use before multiplying by the j -th coefficient of the alternative chroma filter with index altIdx . It is a requirement of bitstream conformance that the values of $\text{alf_chroma_clip_idx}[\text{altIdx}][j]$ with $\text{altIdx}=0 \dots$

$\text{alf_chroma_num_alt_filters_minus1}$, $j=0 \dots 5$ shall be in the range of 0 to 3, inclusive.

The chroma filter clipping values $\text{AlfClip.sub.C}[\text{adaptation_parameter_set_id}][\text{altIdx}]$ with elements

$\text{AlfClip.sub.C}[\text{adaptation_parameter_set_id}][\text{altIdx}][j]$, with $\text{altIdx}=0 \dots$

$\text{alf_chroma_num_alt_filters_minus1}$, $j=0 \dots 5$ are derived as specified in Table 8 depending on BitDepth and clipIdx set equal to $\text{alf_chroma_clip_idx}[\text{altIdx}][j]$.

(49) TABLE-US-00024 TABLE 8 Specification AlfClip depending on BitDepth and clipIdx

BitDepth 0 1 2 3 8 2.sup.8 2.sup.5 2.sup.3 2.sup.1 9 2.sup.9 2.sup.6 2.sup.4 2.sup.2 10 2.sup.10 2.sup.7 2.sup.5 2.sup.3 11 2.sup.11 2.sup.8 2.sup.6 2.sup.4 12 2.sup.12 2.sup.9 2.sup.7 2.sup.5 13 2.sup.13 .sup. 2.sup.10 2.sup.8 2.sup.6 14 2.sup.14 .sup. 2.sup.11 2.sup.9 2.sup.7 15 2.sup.15 .sup. 2.sup.12 .sup. 2.sup.10 2.sup.8 16 2.sup.16 .sup. 2.sup.13 .sup. 2.sup.11 2.sup.9

lmcs_min_bin_idx specifies the minimum bin index used in the luma mapping with chroma scaling construction process. The value of lmcs_min_bin_idx shall be in the range of 0 to 15, inclusive.

lmcs_delta_max_bin_idx specifies the delta value between 15 and the maximum bin index

LmcsMaxBinIdx used in the luma mapping with chroma scaling construction process. The value of lmcs_delta_max_bin_idx shall be in the range of 0 to 15, inclusive. The value of LmcsMaxBinIdx is set equal to 15-lmcs_delta_max_bin_idx. The value of LmcsMaxBinIdx shall be greater than or equal to lmcs_min_bin_idx.

lmcs_delta_cw_prec_minus1 plus 1 specifies the number of bits used for the representation of the syntax lmcs_delta_abs_cw[i]. The value of lmcs_delta_cw_prec_minus1 shall be in the range of 0 to BitDepth-2, inclusive.

lmcs_delta_abs_cw[i] specifies the absolute delta codeword value for the ith bin.

lmcs_delta_sign_cw_flag[i] specifies the sign of the variable lmcsDeltaCW[i] as follows: If lmcs_delta_sign_cw_flag[i] is equal to 0, lmcsDeltaCW[i] is a positive value. Otherwise (lmcs_delta_sign_cw_flag[i] is not equal to 0), lmcsDeltaCW[i] is a negative value.

When lmcs_delta_sign_cw_flag[i] is not present, it is inferred to be equal to 0.

The variable OrgCW is derived as follows:

$$\text{OrgCW} = (1 \ll \text{BitDepth}) / 16 \quad (98)$$

The variable lmcsDeltaCW[i], with $i = \text{lmcs_min_bin_idx} \dots \text{LmcsMaxBinIdx}$, is derived as follows:

$$\text{lmcsDeltaCW}[i] = (1 - 2 * \text{lmcs_delta_sign_cw_flag}[i]) * \text{lmcs_delta_abs_cw}[i] \quad (99)$$

The variable lmcsCW[i] is derived as follows: For $i = 0 \dots \text{lmcs_min_bin_idx} - 1$, lmcsCW[i] is set equal 0.

For $i = \text{lmcs_min_bin_idx} \dots \text{LmcsMaxBinIdx}$, the following applies:

$$\text{lmcsCW}[i] = \text{OrgCW} + \text{lmcsDeltaCW}[i] \quad (100)$$

(50) The value of lmcsCW[i] shall be in the range of $(\text{OrgCW} \gg 3)$ to $(\text{OrgCW} \ll 3 - 1)$, inclusive. For $i = \text{LmcsMaxBinIdx} + 1 \dots 15$, lmcsCW[i] is set equal 0.

It is a requirement of bitstream conformance that the following condition is true:

$$\sum_{i=0}^{\text{sub.i}=0}^{\text{sup.i}=15} \text{lmcsCW}[i] \leq (1 \ll \text{BitDepth}) - 1 \quad (101)$$

The variable InputPivot[i], with $i = 0 \dots 16$, is derived as follows:

$$\text{InputPivot}[i] = i * \text{OrgCW} \quad (102)$$

The variable LmcsPivot[i] with $i = 0 \dots 16$, the variables ScaleCoeff[i] and InvScaleCoeff[i] with $i = 0 \dots 15$, are derived as follows:

$$(51) \text{ TABLE-US-00025 } \begin{aligned} &\text{LmcsPivot}[0] = 0; \text{ for } (i = 0; i \leq 15; i++) \{ \\ &\quad \text{LmcsPivot}[i + 1] = \text{LmcsPivot}[i] + \text{lmcsCW}[i] \\ &\quad \text{ScaleCoeff}[i] = (\text{lmcsCW}[i] * (1 \ll 11) + (1 \ll (\text{Log2}(\text{OrgCW}) - 1))) \gg (\text{Log2}(\text{OrgCW})) \\ &\quad \text{if } (\text{lmcsCW}[i] = 0) \text{ (103) } \quad \text{InvScaleCoeff}[i] = 0 \quad \text{else} \quad \text{InvScaleCoeff}[i] = \text{OrgCW} * (1 \ll 11) / \text{lmcsCW}[i] \} \end{aligned}$$

It is a requirement of bitstream conformance that, for $i = \text{lmcs_min_bin_idx} \dots \text{LmcsMaxBinIdx}$, when the value of LmcsPivot[i] is not a multiple of $1 \ll (\text{BitDepth} - 5)$, the value of $(\text{LmcsPivot}[i] \gg (\text{BitDepth} - 5))$ shall not be equal to the value of $(\text{LmcsPivot}[i + 1] \gg (\text{BitDepth} - 5))$.

lmcs_delta_abs_crs specifies the absolute codeword value of the variable lmcsDeltaCrs. The value of lmcs_delta_abs_crs shall be in the range of 0 and 7, inclusive. When not present, lmcs_delta_abs_crs is inferred to be equal to 0.

lmcs_delta_sign_crs_flag specifies the sign of the variable lmcsDeltaCrs. When not present, lmcs_delta_sign_crs_flag is inferred to be equal to 0.

The variable lmcsDeltaCrs is derived as follows:

$$\text{lmcsDeltaCrs} = (1 - 2 * \text{lmcs_delta_sign_crs_flag}) * \text{lmcs_delta_abs_crs} \quad (104)$$

It is a requirement of bitstream conformance that, when lmcsCW[i] is not equal to 0,

$(\text{lmcsCW}[i] + \text{lmcsDeltaCrs})$ shall be in the range of $(\text{OrgCW} \gg 3)$ to $((\text{OrgCW} \ll 3) - 1)$, inclusive.

The variable ChromaScaleCoeff[i], with $i = 0 \dots 15$, is derived as follows:

$$(52) \text{ TABLE-US-00026 } \begin{aligned} &\text{if } (\text{lmcsCW}[i] = 0) \quad \text{ChromaScaleCoeff}[i] = (1 \ll 11) \text{ else} \\ &\text{ChromaScaleCoeff}[i] = \text{OrgCW} * (1 \ll 11) / (\text{lmcsCW}[i] + \text{lmcsDeltaCrs}) \end{aligned}$$

scaling_matrix_for_lfnst_disabled_flag equal to 1 specifies that scaling matrices are not applied to blocks coded with LFNST. scaling_matrix_for_lfnst_disabled_flag equal to 0 specifies that the scaling matrices may apply to the blocks coded with LFNST.

scaling_list_chroma_present_flag equal to 1 specifies that chroma scaling lists are present in scaling_list_data(). scaling_list_chroma_present_flag equal to 0 specifies that chroma scaling lists are not present in scaling_list_data(). It is a requirement of bitstream conformance that

scaling_list_chroma_present_flag shall be equal to 0 when ChromaArrayType is equal to 0, and shall be equal to 1 when ChromaArrayType is not equal to 0.

scaling_list_copy_mode_flag[id] equal to 1 specifies that the values of the scaling list are the same as the values of a reference scaling list. The reference scaling list is specified by scaling_list_pred_id_delta[id].

scaling_list_copy_mode_flag[id] equal to 0 specifies that scaling_list_pred_mode_flag is present.

scaling_list_pred_mode_flag[id] equal to 1 specifies that the values of the scaling list can be predicted from a reference scaling list. The reference scaling list is specified by scaling_list_pred_id_delta[id].

scaling_list_pred_mode_flag[id] equal to 0 specifies that the values of the scaling list are explicitly signalled. When not present, the value of scaling_list_pred_mode_flag[id] is inferred to be equal to 0.

scaling_list_pred_id_delta[id] specifies the reference scaling list used to derive the predicted scaling matrix ScalingMatrixPred[id]. When not present, the value of scaling_list_pred_id_delta[id] is inferred to be equal to 0. The value of scaling_list_pred_id_delta[id] shall be in the range of 0 to maxIdDelta with maxIdDelta derived depending on id as follows:

$$\text{maxIdDelta} = (\text{id} < 2) ? \text{id} : ((\text{id} < 8) ? (\text{id} - 2) : (\text{id} - 8)) \quad (106)$$

The variables refId and matrixSize are derived as follows:

$$\text{refId} = \text{id} - \text{scaling_list_pred_id_delta}[\text{id}] \quad (107)$$

$$\text{matrixSize} = (\text{id} < 2) ? 2 : ((\text{id} < 8) ? 4 : 8) \quad (108)$$

The (matrixSize)×(matrixSize) array ScalingMatrixPred[x][y] with x=0 . . . matrixSize-1, y=0 . . .

matrixSize-1 and the variable ScalingMatrixDCPred are derived as follows: When both

scaling_list_copy_mode_flag[id] and scaling_list_pred_mode_flag[id] are equal to 0, all elements of ScalingMatrixPred are set equal to 8, and the value of ScalingMatrixDCPred is set equal to 8. Otherwise, when scaling_list_pred_id_delta[id] is equal to 0, all elements of ScalingMatrixPred are set equal to 16, and ScalingMatrixDCPred is set equal to 16. Otherwise (either scaling_list_copy_mode_flag[id] or scaling_list_pred_mode_flag[id] is equal to 1 and scaling_list_pred_id_delta[id] is greater than 0),

ScalingMatrixPred is set equal to ScalingMatrixRec[refId], and the following applies for

ScalingMatrixDCPred: If refId is greater than 13, ScalingMatrixDCPred is set equal to

ScalingMatrixDCRec[refId-14]. Otherwise (refId is less than or equal to 13), ScalingMatrixDCPred is set equal to ScalingMatrixPred[0][0].

scaling_list_dc_coef[id-14] is used to derive the value of the variable ScalingMatrixDC[id-14] when id is greater than 13 as follows:

$$\text{ScalingMatrixDCRec}[\text{id}-14] = (\text{ScalingMatrixDCPred} + \text{scaling_list_dc_coef}[\text{id}-14]) \& 255 \quad (109)$$

When not present, the value of scaling_list_dc_coef[id-14] is inferred to be equal to 0. The value of scaling_list_dc_coef[id-14] shall be in the range of -128 to 127, inclusive. The value of ScalingMatrixDCRec[id-14] shall be greater than 0.

scaling_list_delta_coef[id][i] specifies the difference between the current matrix coefficient ScalingList[id][i] and the previous matrix coefficient ScalingList[id][i-1], when

scaling_list_copy_mode_flag[id] is equal to 0. The value of scaling_list_delta_coef[id][i] shall be in the range of -128 to 127, inclusive. When scaling_list_copy_mode_flag[id] is equal to 1, all elements of ScalingList[id] are set equal to 0.

The (matrixSize)×(matrixSize) array ScalingMatrixRec[id] is derived as follows:

$$(53) \text{ TABLE-US-00027 } \text{ScalingMatrixRec}[\text{id}][\text{x}][\text{y}] = (\text{ScalingMatrixPred}[\text{x}][\text{y}] + (110)$$

$$\text{ScalingList}[\text{id}][\text{k}]) \& 255 \text{ with } \text{k} = 0 \dots (\text{matrixSize} * \text{matrixSize} - 1), \text{X} = \text{DiagScanOrder}[\text{Log2}(\text{matrixSize})][\text{Log2}(\text{matrixSize})][\text{k}][0], \text{ and } \text{y} = \text{DiagScanOrder}[\text{Log2}(\text{matrixSize})][\text{Log2}(\text{matrixSize})][\text{k}][1]$$

The value of ScalingMatrixRec[id][x][y] shall be greater than 0.

3.8. PH Syntax and Semantics

In the latest VVC draft text, the PH syntax and semantics are as follows:

(54) TABLE-US-00028 Descriptor picture_header_rbsp() { picture_header_structure()

rbbsp_trailing_bits() }

The PH RBSP contains a PH syntax structure, i.e., picture_header_structure().

```
(55) TABLE-US-00029 Descriptor picture_header_structure( ) { gdr_or_irap_pic_flag u(1)  if(
gdr_or_irap_pic_flag )      gdr_pic_flag u(1)  ph_inter_slice_allowed_flag u(1)  if(
ph_inter_slice_allowed_flag )      ph_intra_slice_allowed_flag u(1)  non_reference_picture_flag u(1)
ph_pic_parameter_set_id ue(v)  ph_pic_order_cnt_lsb u(v)  if( gdr_or_irap_pic_flag )
no_output_of_prior_pics_flag u(1)  if( gdr_pic_flag )      recovery_poc_cnt ue(v)  for( i = 0; i <
NumExtraPhBits; i++ )      ph_extra_bit[ i ] u(1)  if( sps_poc_msb_flag ) {
ph_poc_msb_present_flag u(1)      if( ph_poc_msb_present_flag )      poc_msb_val u(v)  }  if(
sps_alf_enabled_flag && alf_info_in_ph_flag ) {      ph_alf_enabled_flag u(1)      if(
ph_alf_enabled_flag ) {      ph_num_alf_aps_ids_luma u(3)      for( i = 0; i <
ph_num_alf_aps_ids_luma; i++ )      ph_alf_aps_id_luma[ i ] u(3)      if( ChromaArrayType !=
0 )      ph_alf_chroma_idc u(2)      if( ph_alf_chroma_idc > 0 )
ph_alf_aps_id_chroma u(3)      if( sps_ccalf_enabled_flag ) {      ph_cc_alf_cb_enabled_flag
u(1)      if( ph_cc_alf_cb_enabled_flag )      ph_cc_alf_cb_aps_id u(3)
ph_cc_alf_cr_enabled_flag u(1)      if( ph_cc_alf_cr_enabled_flag )
ph_cc_alf_cr_aps_id u(3)      }      }      }  if( sps_lmcs_enabled_flag ) {
ph_lmcs_enabled_flag u(1)      if( ph_lmcs_enabled_flag ) {      ph_lmcs_aps_id u(2)      if(
ChromaArrayType != 0 )      ph_chroma_residual_scale_flag u(1)      }      }  if(
sps_scaling_list_enabled_flag ) {      ph_scaling_list_present_flag u(1)      if(
ph_scaling_list_present_flag )      ph_scaling_list_aps_id u(3)      }  if(
sps_virtual_boundaries_enabled_flag && !sps_virtual_boundaries_present_flag ) {
ph_virtual_boundaries_present_flag u(1)      if( ph_virtual_boundaries_present_flag ) {
ph_num_ver_virtual_boundaries u(2)      for( i = 0; i < ph_num_ver_virtual_boundaries; i++ )
ph_virtual_boundaries_pos_x[ i ] u(13)      ph_num_hor_virtual_boundaries u(2)
for( i = 0; i < ph_num_hor_virtual_boundaries; i++ )      ph_virtual_boundaries_pos_y[ i ] u(13)
}      }  if( output_flag_present_flag )      pic_output_flag u(1)  if( rpl_info_in_ph_flag )
ref_pic_lists( )  if( partition_constraints_override_enabled_flag )
partition_constraints_override_flag u(1)  if( ph_intra_slice_allowed_flag ) {      if(
partition_constraints_override_flag ) {      ph_log2_diff_min_qt_min_cb_intra_slice_luma ue(v)
ph_max_mtt_hierarchy_depth_intra_slice_luma ue(v)      if(
ph_max_mtt_hierarchy_depth_intra_slice_luma != 0 ) {
ph_log2_diff_max_bt_min_qt_intra_slice_luma ue(v)
ph_log2_diff_max_tt_min_qt_intra_slice_luma ue(v)      }      if( qtbtt_dual_tree_intra_flag ) {
ph_log2_diff_min_qt_min_cb_intra_slice_chroma ue(v)
ph_max_mtt_hierarchy_depth_intra_slice_chroma ue(v)      if(
ph_max_mtt_hierarchy_depth_intra_slice_chroma != 0 ) {
ph_log2_diff_max_bt_min_qt_intra_slice_chroma ue(v)
ph_log2_diff_max_tt_min_qt_intra_slice_chroma ue(v)      }      }      }  if(
cu_qp_delta_enabled_flag )      ph_cu_qp_delta_subdiv_intra_slice ue(v)      if(
pps_cu_chroma_qp_offset_list_enabled_flag )      ph_cu_chroma_qp_offset_subdiv_intra_slice ue(v)
}  if( ph_inter_slice_allowed_flag ) {      if( partition_constraints_override_flag ) {
ph_log2_diff_min_qt_min_cb_inter_slice ue(v)      ph_max_mtt_hierarchy_depth_inter_slice ue(v)
if( ph_max_mtt_hierarchy_depth_inter_slice != 0 ) {
ph_log2_diff_max_bt_min_qt_inter_slice ue(v)      ph_log2_diff_max_tt_min_qt_inter_slice ue(v)
}      }      if( cu_qp_delta_enabled_flag )      ph_cu_qp_delta_subdiv_inter_slice ue(v)
if( pps_cu_chroma_qp_offset_list_enabled_flag )
ph_cu_chroma_qp_offset_subdiv_inter_slice ue(v)      if( sps_temporal_mvp_enabled_flag ) {
ph_temporal_mvp_enabled_flag u(1)      if( ph_temporal_mvp_enabled_flag && rpl_info_in_ph_flag
) {      ph_collocated_from_l0_flag u(1)      if( ( ph_collocated_from_l0_flag &&
num_ref_entries[ 0 ][ RplIdx[ 0 ] ] > 1 ) ||      ( !ph_collocated_from_l0_flag
&& num_ref_entries[ 1 ][ RplIdx[ 1 ] ] > 1 ) )      ph_collocated_ref_idx ue(v)
```

```

    }
    }    mvd_l1_zero_flag u(1)    if( sps_fpel_mmvd_enabled_flag )
ph_fpel_mmvd_enabled_flag u(1)    if( sps_bdof_pic_present_flag )    ph_disable_bdof_flag u(1)
    if( sps_dmvr_pic_present_flag )    ph_disable_dmvr_flag u(1)    if(
sps_prof_pic_present_flag )    ph_disable_prof_flag u(1)    if( ( pps_weighted_pred_flag ||
pps_weighted_bipred_flag ) && wp_info_in_ph_flag )    pred_weight_table( )    }    if(
qp_delta_info_in_ph_flag )    ph_qp_delta se(v)    if( sps_joint_cbr_enabled_flag )
ph_joint_cbr_sign_flag u(1)    if( sps_sao_enabled_flag && sao_info_in_ph_flag ) {
ph_sao_luma_enabled_flag u(1)    if( ChromaArrayType != 0 )    ph_sao_chroma_enabled_flag
u(1)    }    if( sps_dep_quant_enabled_flag )    ph_dep_quant_enabled_flag u(1)    if(
sps_sign_data_hiding_enabled_flag && !ph_dep_quant_enabled_flag )
pic_sign_data_hiding_enabled_flag u(1)    if( deblocking_filter_override_enabled_flag &&
dbf_info_in_ph_flag ) {    ph_deblocking_filter_override_flag u(1)    if(
ph_deblocking_filter_override_flag ) {    ph_deblocking_filter_disabled_flag u(1)    if(
!ph_deblocking_filter_disabled_flag ) {    ph_beta_offset_div2 se(v)    ph_tc_offset_div2
se(v)    ph_cb_beta_offset_div2 se(v)    ph_cb_tc_offset_div2 se(v)
ph_cr_beta_offset_div2 se(v)    ph_cr_tc_offset_div2 se(v)    }    }    }    if(
picture_header_extension_present_flag ) {    ph_extension_length ue(v)    for( i = 0; i <
ph_extension_length; i++)    ph_extension_data_byte[ i ] u(8)    } }

```

The PH syntax structure contains information that is common for all slices of the coded picture associated with the PH syntax structure.

gdr_or_irap_pic_flag equal to 1 specifies that the current picture is a GDR or TRAP picture.

gdr_or_irap_pic_flag equal to 0 specifies that the current picture may or may not be a GDR or IRAP picture.

gdr_pic_flag equal to 1 specifies the picture associated with the PH is a GDR picture. **gdr_pic_flag** equal to 0 specifies that the picture associated with the PH is not a GDR picture. When not present, the value of **gdr_pic_flag** is inferred to be equal to 0. When **gdr_enabled_flag** is equal to 0, the value of **gdr_pic_flag** shall be equal to 0.

ph_inter_slice_allowed_flag equal to 0 specifies that all coded slices of the picture have **slice_type** equal to 2. **ph_inter_slice_allowed_flag** equal to 1 specifies that there may or may not be one or more coded slices in the picture that have **slice_type** equal to 0 or 1.

ph_intra_slice_allowed_flag equal to 0 specifies that all coded slices of the picture have **slice_type** equal to 0 or 1. **ph_intra_slice_allowed_flag** equal to 1 specifies that there may or may not be one or more coded slices in the picture that have **slice_type** equal to 2. When not present, the value of **ph_intra_slice_allowed_flag** is inferred to be equal to 1. NOTE 1—For bitstreams that are supposed to work subpicture based bitstream merging without the need of changing PH NAL units, the encoder is expected to set the values of both **ph_inter_slice_allowed_flag** and **ph_intra_slice_allowed_flag** equal to 1.

non_reference_picture_flag equal to 1 specifies the picture associated with the PH is never used as a reference picture. **non_reference_picture_flag** equal to 0 specifies the picture associated with the PH may or may not be used as a reference picture.

ph_pic_parameter_set_id specifies the value of **pps_pic_parameter_set_id** for the PPS in use. The value of **ph_pic_parameter_set_id** shall be in the range of 0 to 63, inclusive.

It is a requirement of bitstream conformance that the value of **TemporalId** of the PH shall be greater than or equal to the value of **TemporalId** of the PPS that has **pps_pic_parameter_set_id** equal to **ph_pic_parameter_set_id**.

ph_pic_order_cnt_lsb specifies the picture order count modulo **MaxPicOrderCntLsb** for the current picture. The length of the **ph_pic_order_cnt_lsb** syntax element is **log2_max_pic_order_cnt_lsb_minus4+4** bits. The value of the **ph_pic_order_cnt_lsb** shall be in the range of 0 to **MaxPicOrderCntLsb-1**, inclusive.

no_output_of_prior_pics_flag affects the output of previously-decoded pictures in the DPB after the decoding of a CLVSS picture that is not the first picture in the bitstream as specified in Annex C.

recovery_poc_cnt specifies the recovery point of decoded pictures in output order. If the current picture is a GDR picture that is associated with the PH, and there is a picture **picA** that follows the current GDR

picture in decoding order in the CLVS that has PicOrderCntVal equal to the PicOrderCntVal of the current GDR picture plus the value of recovery_poc_cnt, the picture picA is referred to as the recovery point picture. Otherwise, the first picture in output order that has PicOrderCntVal greater than the PicOrderCntVal of the current picture plus the value of recovery_poc_cnt is referred to as the recovery point picture. The recovery point picture shall not precede the current GDR picture in decoding order. The value of recovery_poc_cnt shall be in the range of 0 to MaxPicOrderCntLsb-1, inclusive.

When the current picture is a GDR picture, the variable RpPicOrderCntVal is derived as follows:

$$\text{RpPicOrderCntVal} = \text{PicOrderCntVal} + \text{recovery_poc_cnt} \quad (82)$$
 NOTE 2—When `gdr_enabled_flag` is equal to 1 and PicOrderCntVal of the current picture is greater than or equal to RpPicOrderCntVal of the associated GDR picture, the current and subsequent decoded pictures in output order are exact match to the corresponding pictures produced by starting the decoding process from the previous IRAP picture, when present, preceding the associated GDR picture in decoding order.

`ph_extra_bit[i]` may be equal to 1 or 0. Decoders conforming to this version of this Specification shall ignore the value of `ph_extra_bit[i]`. Its value does not affect decoder conformance to profiles specified in this version of specification.

`ph_poc_msb_present_flag` equal to 1 specifies that the syntax element `poc_msb_val` is present in the PH. `ph_poc_msb_present_flag` equal to 0 specifies that the syntax element `poc_msb_val` is not present in the PH. When `vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]]` is equal to 0 and there is a picture in the current AU in a reference layer of the current layer, the value of `ph_poc_msb_present_flag` shall be equal to 0. `poc_msb_val` specifies the POC MSB value of the current picture. The length of the syntax element `poc_msb_val` is `poc_msb_len_minus1+1` bits.

`ph_alf_enabled_flag` equal to 1 specifies that adaptive loop filter is enabled for all slices associated with the PH and may be applied to Y, Cb, or Cr color component in the slices. `ph_alf_enabled_flag` equal to 0 specifies that adaptive loop filter may be disabled for one, or more, or all slices associated with the PH. When not present, `ph_alf_enabled_flag` is inferred to be equal to 0.

`ph_num_alf_aps_ids_luma` specifies the number of ALF APSs that the slices associated with the PH refers to.

`ph_alf_aps_id_luma[i]` specifies the `adaptation_parameter_set_id` of the *i*-th ALF APS that the luma component of the slices associated with the PH refers to.

The value of `alf_luma_filter_signal_flag` of the APS NAL unit having `aps_params_type` equal to ALF_APS and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_luma[i]` shall be equal to 1.

The TemporalId of the APS NAL unit having `aps_params_type` equal to ALF_APS and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_luma[i]` shall be less than or equal to the TemporalId of the picture associated with the PH.

`ph_alf_chroma_idc` equal to 0 specifies that the adaptive loop filter is not applied to Cb and Cr color components. `ph_alf_chroma_idc` equal to 1 indicates that the adaptive loop filter is applied to the Cb color component. `ph_alf_chroma_idc` equal to 2 indicates that the adaptive loop filter is applied to the Cr color component. `ph_alf_chroma_idc` equal to 3 indicates that the adaptive loop filter is applied to Cb and Cr color components. When `ph_alf_chroma_idc` is not present, it is inferred to be equal to 0.

`ph_alf_aps_id_chroma` specifies the `adaptation_parameter_set_id` of the ALF APS that the chroma component of the slices associated with the PH refers to.

The value of `alf_chroma_filter_signal_flag` of the APS NAL unit having `aps_params_type` equal to ALF_APS and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_chroma` shall be equal to 1.

The TemporalId of the APS NAL unit having `aps_params_type` equal to ALF_APS and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_chroma` shall be less than or equal to the TemporalId of the picture associated with the PH.

`ph_cc_alf_cb_enabled_flag` equal to 1 specifies that cross-component filter for Cb color component is enabled for all slices associated with the PH and may be applied to Cb color component in the slices.

`ph_cc_alf_cb_enabled_flag` equal to 0 specifies that cross-component filter for Cb color component may be disabled for one, or more, or all slices associated with the PH. When not present,

`ph_cc_alf_cb_enabled_flag` is inferred to be equal to 0.

`ph_cc_alf_cb_aps_id` specifies the `adaptation_parameter_set_id` of the ALF APS that the Cb color component of the slices associated with the PH refers to.

The value of `alf_cc_cb_filter_signal_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_cc_alf_cb_aps_id` shall be equal to 1. The `TemporalId` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_cc_alf_cb_aps_id` shall be less than or equal to the `TemporalId` of the picture associated with the PH.

`ph_cc_alf_cr_enabled_flag` equal to 1 specifies that cross-component filter for Cr color component is enabled for all slices associated with the PH and may be applied to Cr color component in the slices. `ph_cc_alf_cr_enabled_flag` equal to 0 specifies that cross-component filter for Cr color component may be disabled for one, or more, or all slices associated with the PH. When not present, `ph_cc_alf_cr_enabled_flag` is inferred to be equal to 0.

`ph_cc_alf_cr_aps_id` specifies the `adaptation_parameter_set_id` of the ALF APS that the Cr color component of the slices associated with the PH refers to.

The value of `alf_cc_cr_filter_signal_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_cc_alf_cr_aps_id` shall be equal to 1. The `TemporalId` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_cc_alf_cr_aps_id` shall be less than or equal to the `TemporalId` of the picture associated with the PH. `ph_lmcs_enabled_flag` equal to 1 specifies that luma mapping with chroma scaling is enabled for all slices associated with the PH. `ph_lmcs_enabled_flag` equal to 0 specifies that luma mapping with chroma scaling may be disabled for one, or more, or all slices associated with the PH. When not present, the value of `ph_lmcs_enabled_flag` is inferred to be equal to 0.

`ph_lmcs_aps_id` specifies the `adaptation_parameter_set_id` of the LMCS APS that the slices associated with the PH refers to. The `TemporalId` of the APS NAL unit having `aps_params_type` equal to `LMCS_APS` and `adaptation_parameter_set_id` equal to `ph_lmcs_aps_id` shall be less than or equal to the `TemporalId` of the picture associated with PH.

`ph_chroma_residual_scale_flag` equal to 1 specifies that chroma residual scaling is enabled for the all slices associated with the PH. `ph_chroma_residual_scale_flag` equal to 0 specifies that chroma residual scaling may be disabled for one, or more, or all slices associated with the PH. When `ph_chroma_residual_scale_flag` is not present, it is inferred to be equal to 0.

`ph_scaling_list_present_flag` equal to 1 specifies that the scaling list data used for the slices associated with the PH is derived based on the scaling list data contained in the referenced scaling list APS. `ph_scaling_list_present_flag` equal to 0 specifies that the scaling list data used for the slices associated with the PH is set to be equal to 16. When not present, the value of `ph_scaling_list_present_flag` is inferred to be equal to 0.

`ph_scaling_list_aps_id` specifies the `adaptation_parameter_set_id` of the scaling list APS. The `TemporalId` of the APS NAL unit having `aps_params_type` equal to `SCALING_APS` and `adaptation_parameter_set_id` equal to `ph_scaling_list_aps_id` shall be less than or equal to the `TemporalId` of the picture associated with PH.

`ph_virtual_boundaries_present_flag` equal to 1 specifies that information of virtual boundaries is signalled in the PH. `ph_virtual_boundaries_present_flag` equal to 0 specifies that information of virtual boundaries is not signalled in the PH. When there is one or more than one virtual boundaries signalled in the PH, the in-loop filtering operations are disabled across the virtual boundaries in the picture. The in-loop filtering operations include the deblocking filter, sample adaptive offset filter, and adaptive loop filter operations. When not present, the value of `ph_virtual_boundaries_present_flag` is inferred to be equal to 0.

It is a requirement of bitstream conformance that, when `subpic_info_present_flag` is equal to 1, the value of `ph_virtual_boundaries_present_flag` shall be equal to 0.

The variable `VirtualBoundariesPresentFlag` is derived as follows:

(56) `TABLE-US-00030 VirtualBoundariesPresentFlag = 0 if( sps_virtual_boundaries_enabled_flag )`
`VirtualBoundariesPresentFlag = sps_virtual_boundaries_present_flag ||`
`ph_virtual_boundaries_present_flag` (83)

`ph_num_ver_virtual_boundaries` specifies the number of `ph_virtual_boundaries_pos_x[i]` syntax elements that are present in the PH. When `ph_num_ver_virtual_boundaries` is not present, it is inferred to be equal to 0.

The variable `NumVerVirtualBoundaries` is derived as follows:

(57) TABLE-US-00031 NumVerVirtualBoundaries = 0 if(sps_virtual_boundaries_enabled_flag)

NumVerVirtualBoundaries = sps_virtual_boundaries_present_flag ?

sps_num_ver_virtual_boundaries : (84) ph_num_ver_virtual_boundaries

ph_virtual_boundaries_pos_x[i] specifies the location of the i-th vertical virtual boundary in units of luma samples divided by 8. The value of ph_virtual_boundaries_pos_x[i] shall be in the range of 1 to $\text{Ceil}(\text{pic_width_in_luma_samples} \div 8) - 1$, inclusive.

The list VirtualBoundariesPosX[i] for i ranging from 0 to NumVerVirtualBoundaries-1, inclusive, in units of luma samples, specifying the locations of the vertical virtual boundaries, is derived as follows:

(58) TABLE-US-00032 for(i = 0; i < NumVerVirtualBoundaries; i++) VirtualBoundariesPosX[i] = (

sps_virtual_boundaries_present_flag ? sps_virtual_boundaries_pos_x[i] : (85)

ph_virtual_boundaries_pos_x[i]) * 8

The distance between any two vertical virtual boundaries shall be greater than or equal to CtbSizeY luma samples.

ph_num_hor_virtual_boundaries specifies the number of ph_virtual_boundaries_pos_y[i] syntax elements that are present in the PH. When ph_num_hor_virtual_boundaries is not present, it is inferred to be equal to 0.

The parameter NumHorVirtualBoundaries is derived as follows:

(59) TABLE-US-00033 NumHorVirtualBoundaries = 0 if(sps_virtual_boundaries_enabled_flag)

NumHorVirtualBoundaries = sps_virtual_boundaries_present_flag ?

sps_num_hor_virtual_boundaries : (86) ph_num_hor_virtual_boundaries

When sps_virtual_boundaries_enabled_flag is equal to 1 and ph_virtual_boundaries_present_flag is equal to 1, the sum of ph_num_ver_virtual_boundaries and ph_num_hor_virtual_boundaries shall be greater than 0. ph_virtual_boundaries_pos_y[i] specifies the location of the i-th horizontal virtual boundary in units of luma samples divided by 8. The value of ph_virtual_boundaries_pos_y[i] shall be in the range of 1 to $\text{Ceil}(\text{pic_height_in_luma_samples} \div 8) - 1$, inclusive.

The list VirtualBoundariesPosY[i] for i ranging from 0 to NumHorVirtualBoundaries-1, inclusive, in units of luma samples, specifying the locations of the horizontal virtual boundaries, is derived as follows:

(60) TABLE-US-00034 for(i = 0; i < NumHorVirtualBoundaries; i++) VirtualBoundariesPosY[i] = (

sps_virtual_boundaries_present_flag ? sps_virtual_boundaries_pos_y[i] : (87)

ph_virtual_boundaries_pos_y[i]) * 8

The distance between any two horizontal virtual boundaries shall be greater than or equal to CtbSizeY luma samples.

pic_output_flag affects the decoded picture output and removal processes as specified in Annex C. When pic_output_flag is not present, it is inferred to be equal to 1.

partition_constraints_override_flag equal to 1 specifies that partition constraint parameters are present in the PH. partition_constraints_override_flag equal to 0 specifies that partition constraint parameters are not present in the PH. When not present, the value of partition_constraints_override_flag is inferred to be equal to 0.

ph_log2_diff_min_qt_min_cb_intra_slice_luma specifies the difference between the base 2 logarithm of the minimum size in luma samples of a luma leaf block resulting from quadtree splitting of a CTU and the base 2 logarithm of the minimum coding block size in luma samples for luma CUs in the slices with slice_type equal to 2 (I) associated with the PH. The value of

ph_log2_diff_min_qt_min_cb_intra_slice_luma shall be in the range of 0 to $\text{CtbLog2SizeY} - \text{MinCbLog2SizeY}$, inclusive. When not present, the value of

ph_log2_diff_min_qt_min_cb_luma is inferred to be equal to

sps_log2_diff_min_qt_min_cb_intra_slice_luma.

ph_max_mtt_hierarchy_depth_intra_slice_luma specifies the maximum hierarchy depth for coding units resulting from multi-type tree splitting of a quadtree leaf in slices with slice_type equal to 2 (I) associated with the PH. The value of ph_max_mtt_hierarchy_depth_intra_slice_luma shall be in the range of 0 to $2 * (\text{CtbLog2SizeY} - \text{MinCbLog2SizeY})$, inclusive. When not present, the value of

ph_max_mtt_hierarchy_depth_intra_slice_luma is inferred to be equal to

sps_max_mtt_hierarchy_depth_intra_slice_luma.

ph_log2_diff_max_bt_min_qt_intra_slice_luma specifies the difference between the base 2 logarithm of

the maximum size (width or height) in luma samples of a luma coding block that can be split using a binary split and the minimum size (width or height) in luma samples of a luma leaf block resulting from quadtree splitting of a CTU in slices with slice_type equal to 2 (I) associated with the PH. The value of `ph_log2_diff_max_bt_min_qt_intra_slice_luma` shall be in the range of 0 to $\text{CtbLog2SizeY} - \text{MinQtLog2SizeIntraY}$, inclusive. When not present, the value of `ph_log2_diff_max_bt_min_qt_intra_slice_luma` is inferred to be equal to `sps_log2_diff_max_bt_min_qt_intra_slice_luma`.

`ph_log2_diff_max_tt_min_qt_intra_slice_luma` specifies the difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a luma coding block that can be split using a ternary split and the minimum size (width or height) in luma samples of a luma leaf block resulting from quadtree splitting of a CTU in slices with slice_type equal to 2 (I) associated with the PH. The value of `ph_log2_diff_max_tt_min_qt_intra_slice_luma` shall be in the range of 0 to $\text{CtbLog2SizeY} - \text{MinQtLog2SizeIntraY}$, inclusive. When not present, the value of `ph_log2_diff_max_a_min_qt_intra_slice_luma` is inferred to be equal to `sps_log2_diff_max_a_min_qt_intra_slice_luma`.

`ph_log2_diff_min_qt_min_cb_intra_slice_chroma` specifies the difference between the base 2 logarithm of the minimum size in luma samples of a chroma leaf block resulting from quadtree splitting of a chroma CTU with treeType equal to DUAL_TREE_CHROMA and the base 2 logarithm of the minimum coding block size in luma samples for chroma CUs with treeType equal to DUAL_TREE_CHROMA in slices with slice_type equal to 2 (I) associated with the PH. The value of `ph_log2_diff_min_qt_min_cb_intra_slice_chroma` shall be in the range of 0 to $\text{CtbLog2SizeY} - \text{MinCbLog2SizeY}$, inclusive. When not present, the value of `ph_log2_diff_min_qt_min_cb_intra_slice_chroma` is inferred to be equal to `sps_log2_diff_min_qt_min_cb_intra_slice_chroma`.

`ph_max_mtt_hierarchy_depth_intra_slice_chroma` specifies the maximum hierarchy depth for chroma coding units resulting from multi-type tree splitting of a chroma quadtree leaf with treeType equal to DUAL_TREE_CHROMA in slices with slice_type equal to 2 (I) associated with the PH. The value of `ph_max_mtt_hierarchy_depth_intra_slice_chroma` shall be in the range of 0 to $2 * (\text{CtbLog2SizeY} - \text{MinCbLog2SizeY})$, inclusive. When not present, the value of `ph_max_mtt_hierarchy_depth_intra_slice_chroma` is inferred to be equal to `sps_max_mtt_hierarchy_depth_intra_slice_chroma`.

`ph_log2_diff_max_bt_min_qt_intra_slice_chroma` specifies the difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a chroma coding block that can be split using a binary split and the minimum size (width or height) in luma samples of a chroma leaf block resulting from quadtree splitting of a chroma CTU with treeType equal to DUAL_TREE_CHROMA in slices with slice_type equal to 2 (I) associated with the PH. The value of `ph_log2_diff_max_bt_min_qt_intra_slice_chroma` shall be in the range of 0 to $\text{CtbLog2SizeY} - \text{MinQtLog2SizeIntraC}$, inclusive. When not present, the value of `ph_log2_diff_max_bt_min_qt_intra_slice_chroma` is inferred to be equal to `sps_log2_diff_max_bt_min_qt_intra_slice_chroma`.

`ph_log2_diff_max_tt_min_qt_intra_slice_chroma` specifies the difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a chroma coding block that can be split using a ternary split and the minimum size (width or height) in luma samples of a chroma leaf block resulting from quadtree splitting of a chroma CTU with treeType equal to DUAL_TREE_CHROMA in slices with slice_type equal to 2 (I) associated with the PH. The value of `ph_log2_diff_max_tt_min_qt_intra_slice_chroma` shall be in the range of 0 to $\text{CtbLog2SizeY} - \text{MinQtLog2SizeIntraC}$, inclusive. When not present, the value of `ph_log2_diff_max_tt_min_qt_intra_slice_chroma` is inferred to be equal to `sps_log2_diff_max_a_min_qt_intra_slice_chroma`.

`ph_cu_qp_delta_subdiv_intra_slice` specifies the maximum `cbSubdiv` value of coding units in intra slice that convey `cu_qp_delta_abs` and `cu_qp_delta_sign_flag`. The value of `ph_cu_qp_delta_subdiv_intra_slice` shall be in the range of 0 to $2 * (\text{CtbLog2SizeY} - \text{MinQtLog2SizeIntraY} + \text{ph_max_mtt_hierarchy_depth_intra_slice_luma})$, inclusive.

When not present, the value of `ph_cu_qp_delta_subdiv_intra_slice` is inferred to be equal to 0.

`ph_cu_chroma_qp_offset_subdiv_intra_slice` specifies the maximum `cbSubdiv` value of coding units in intra slice that convey `cu_chroma_qp_offset_flag`. The value of `ph_cu_chroma_qp_offset_subdiv_intra_slice` shall be in the range of 0 to $2^{*}(\text{CtbLog2SizeY} - \text{MinQtLog2SizeIntraY} + \text{ph_max_mtt_hierarchy_depth_intra_slice_luma})$, inclusive. When not present, the value of `ph_cu_chroma_qp_offset_subdiv_intra_slice` is inferred to be equal to 0.

`ph_log2_diff_min_qt_min_cb_inter_slice` specifies the difference between the base 2 logarithm of the minimum size in luma samples of a luma leaf block resulting from quadtree splitting of a CTU and the base 2 logarithm of the minimum luma coding block size in luma samples for luma CUs in the slices with `slice_type` equal to 0 (B) or 1 (P) associated with the PH. The value of `ph_log2_diff_min_qt_min_cb_inter_slice` shall be in the range of 0 to $\text{CtbLog2SizeY} - \text{MinCbLog2SizeY}$, inclusive. When not present, the value of `ph_log2_diff_min_qt_min_cb_luma` is inferred to be equal to `sps_log2_diff_min_qt_min_cb_inter_slice`.

`ph_max_mtt_hierarchy_depth_inter_slice` specifies the maximum hierarchy depth for coding units resulting from multi-type tree splitting of a quadtree leaf in slices with `slice_type` equal to 0 (B) or 1 (P) associated with the PH. The value of `ph_max_mtt_hierarchy_depth_inter_slice` shall be in the range of 0 to $2^{*}(\text{CtbLog2SizeY} - \text{MinCbLog2SizeY})$, inclusive. When not present, the value of `ph_max_mtt_hierarchy_depth_inter_slice` is inferred to be equal to `sps_max_mtt_hierarchy_depth_inter_slice`.

`ph_log2_diff_max_bt_min_qt_inter_slice` specifies the difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a luma coding block that can be split using a binary split and the minimum size (width or height) in luma samples of a luma leaf block resulting from quadtree splitting of a CTU in the slices with `slice_type` equal to 0 (B) or 1 (P) associated with the PH. The value of `ph_log2_diff_max_bt_min_qt_inter_slice` shall be in the range of 0 to $\text{CtbLog2SizeY} - \text{MinQtLog2SizeInterY}$, inclusive. When not present, the value of `ph_log2_diff_max_bt_min_qt_inter_slice` is inferred to be equal to `sps_log2_diff_max_bt_min_qt_inter_slice`.

`ph_log2_diff_max_tt_min_qt_inter_slice` specifies the difference between the base 2 logarithm of the maximum size (width or height) in luma samples of a luma coding block that can be split using a ternary split and the minimum size (width or height) in luma samples of a luma leaf block resulting from quadtree splitting of a CTU in slices with `slice_type` equal to 0 (B) or 1 (P) associated with the PH. The value of `ph_log2_diff_max_a_min_qt_inter_slice` shall be in the range of 0 to $\text{CtbLog2SizeY} - \text{MinQtLog2SizeInterY}$, inclusive. When not present, the value of `ph_log2_diff_max_tt_min_qt_inter_slice` is inferred to be equal to `sps_log2_diff_max_a_min_qt_inter_slice`.

`ph_cu_qp_delta_subdiv_inter_slice` specifies the maximum `cbSubdiv` value of coding units that in inter slice convey `cu_qp_delta_abs` and `cu_qp_delta_sign_flag`. The value of `ph_cu_qp_delta_subdiv_inter_slice` shall be in the range of 0 to $2^{*}(\text{CtbLog2SizeY} - \text{MinQtLog2SizeInterY} + \text{ph_max_mtt_hierarchy_depth_inter_slice})$, inclusive. When not present, the value of `ph_cu_qp_delta_subdiv_inter_slice` is inferred to be equal to 0.

`ph_cu_chroma_qp_offset_subdiv_inter_slice` specifies the maximum `cbSubdiv` value of coding units in inter slice that convey `cu_chroma_qp_offset_flag`. The value of `ph_cu_chroma_qp_offset_subdiv_inter_slice` shall be in the range of 0 to $2^{*}(\text{CtbLog2SizeY} - \text{MinQtLog2SizeInterY} + \text{ph_max_mtt_hierarchy_depth_inter_slice})$, inclusive. When not present, the value of `ph_cu_chroma_qp_offset_subdiv_inter_slice` is inferred to be equal to 0.

`ph_temporal_mvp_enabled_flag` specifies whether temporal motion vector predictors can be used for inter prediction for slices associated with the PH. If `ph_temporal_mvp_enabled_flag` is equal to 0, the syntax elements of the slices associated with the PH shall be constrained such that no temporal motion vector predictor is used in decoding of the slices. Otherwise (`ph_temporal_mvp_enabled_flag` is equal to 1), temporal motion vector predictors may be used in decoding of the slices associated with the PH. When not present, the value of `ph_temporal_mvp_enabled_flag` is inferred to be equal to 0. When no reference picture in the DPB has the same spatial resolution as the current picture, the value of `ph_temporal_mvp_enabled_flag` shall be equal to 0.

The maximum number of subblock-based merging MVP candidates, `MaxNumSubblockMergeCand`, is derived as follows:

(61) TABLE-US-00035 if(`sps_affine_enabled_flag`) `MaxNumSubblockMergeCand` = 5 – (88)

`five_minus_max_num_subblock_merge_cand` else `MaxNumSubblockMergeCand` =

`sps_sbtmvp_enabled_flag` && `ph_temporal_mvp_enable_flag`

`ph_collocated_from_l0_flag` equal to 1 specifies that the collocated picture used for temporal motion vector prediction is derived from reference picture list 0. `ph_collocated_from_l0_flag` equal to 0 specifies that the collocated picture used for temporal motion vector prediction is derived from reference picture list 1.

`ph_collocated_ref_idx` specifies the reference index of the collocated picture used for temporal motion vector prediction.

When `ph_collocated_from_l0_flag` is equal to 1, `ph_collocated_ref_idx` refers to an entry in reference picture list 0, and the value of `ph_collocated_ref_idx` shall be in the range of 0 to `num_ref_entries[0][RplIdx[0]]–1`, inclusive. When `ph_collocated_from_l0_flag` is equal to 0, `ph_collocated_ref_idx` refers to an entry in reference picture list 1, and the value of `ph_collocated_ref_idx` shall be in the range of 0 to `num_ref_entries[1][RplIdx[1]]–1`, inclusive.

When not present, the value of `ph_collocated_ref_idx` is inferred to be equal to 0.

`mvd_l1_zero_flag` equal to 1 indicates that the `mvd_coding(x0, y0, 1)` syntax structure is not parsed and `MvdL1[x0][y0][compIdx]` and `MvdCpL1[x0][y0][cpIdx][compIdx]` are set equal to 0 for `compIdx=0 . . . 1` and `cpIdx=0 . . . 2`. `mvd_l1_zero_flag` equal to 0 indicates that the `mvd_coding(x0, y0, 1)` syntax structure is parsed.

`ph_fpel_mmvd_enabled_flag` equal to 1 specifies that merge mode with motion vector difference uses integer sample precision in the slices associated with the PH. `ph_fpel_mmvd_enabled_flag` equal to 0 specifies that merge mode with motion vector difference can use fractional sample precision in the slices associated with the PH. When not present, the value of `ph_fpel_mmvd_enabled_flag` is inferred to be 0.

`ph_disable_bdof_flag` equal to 1 specifies that bi-directional optical flow inter prediction based inter bi-prediction is disabled in the slices associated with the PH. `ph_disable_bdof_flag` equal to 0 specifies that bi-directional optical flow inter prediction based inter bi-prediction may or may not be enabled in the slices associated with the PH. When `ph_disable_bdof_flag` is not present, the following applies: If `sps_bdof_enabled_flag` is equal to 1, the value of `ph_disable_bdof_flag` is inferred to be equal to 0. Otherwise (`sps_bdof_enabled_flag` is equal to 0), the value of `ph_disable_bdof_flag` is inferred to be equal to 1.

`ph_disable_dmvr_flag` equal to 1 specifies that decoder motion vector refinement based inter bi-prediction is disabled in the slices associated with the PH. `ph_disable_dmvr_flag` equal to 0 specifies that decoder motion vector refinement based inter bi-prediction may or may not be enabled in the slices associated with the PH.

When `ph_disable_dmvr_flag` is not present, the following applies: If `sps_dmvr_enabled_flag` is equal to 1, the value of `ph_disable_dmvr_flag` is inferred to be equal to 0. Otherwise (`sps_dmvr_enabled_flag` is equal to 0), the value of `ph_disable_dmvr_flag` is inferred to be equal to 1.

`ph_disable_prof_flag` equal to 1 specifies that prediction refinement with optical flow is disabled in the slices associated with the PH. `ph_disable_prof_flag` equal to 0 specifies that prediction refinement with optical flow may or may not be enabled in the slices associated with the PH.

When `ph_disable_prof_flag` is not present, the following applies: If `sps_affine_prof_enabled_flag` is equal to 1, the value of `ph_disable_prof_flag` is inferred to be equal to 0. Otherwise

(`sps_affine_prof_enabled_flag` is equal to 0), the value of `ph_disable_prof_flag` is inferred to be equal to 1.

`ph_qp_delta` specifies the initial value of `Qp.sub.Y` to be used for the coding blocks in the picture until modified by the value of `CuQpDeltaVal` in the coding unit layer.

When `qp_delta_info_in_ph_flag` is equal to 1, the initial value of the `Qp.sub.Y` quantization parameter for all slices of the picture, `SliceQp.sub.Y`, is derived as follows:

`SliceQp.sub.Y`=26+`init_qp_minus26`+`ph_qp_delta` (89)

The value of `SliceQp.sub.Y` shall be in the range of `–QpBdOffset` to `+63`, inclusive.

`ph_joint_eber_sign_flag` specifies whether, in transform units with `to_joint_cbr_residual_flag[x0][y0]` equal to 1, the collocated residual samples of both chroma components have inverted signs. When to

joint_cbr_sign_flag[x0][y0] equal to 1 for a transform unit, ph_joint_cbr_sign_flag equal to 0 specifies that the sign of each residual sample of the Cr (or Cb) component is identical to the sign of the collocated Cb (or Cr) residual sample and ph_joint_cbr_sign_flag equal to 1 specifies that the sign of each residual sample of the Cr (or Cb) component is given by the inverted sign of the collocated Cb (or Cr) residual sample.

ph_sao_luma_enabled_flag equal to 1 specifies that SAO is enabled for the luma component in all slices associated with the PH; ph_sao_luma_enabled_flag equal to 0 specifies that SAO for the luma component may be disabled for one, or more, or all slices associated with the PH. When ph_sao_luma_enabled_flag is not present, it is inferred to be equal to 0.

ph_sao_chroma_enabled_flag equal to 1 specifies that SAO is enabled for the chroma component in all slices associated with the PH; ph_sao_chroma_enabled_flag equal to 0 specifies that SAO for chroma component may be disabled for one, or more, or all slices associated with the PH. When ph_sao_chroma_enabled_flag is not present, it is inferred to be equal to 0.

ph_dep_quant_enabled_flag equal to 0 specifies that dependent quantization is disabled for the current picture. ph_dep_quant_enabled_flag equal to 1 specifies that dependent quantization is enabled for the current picture. When ph_dep_quant_enabled_flag is not present, it is inferred to be equal to 0.

pic_sign_data_hiding_enabled_flag equal to 0 specifies that sign bit hiding is disabled for the current picture. pic_sign_data_hiding_enabled_flag equal to 1 specifies that sign bit hiding is enabled for the current picture. When pic_sign_data_hiding_enabled_flag is not present, it is inferred to be equal to 0.

ph_deblocking_filter_override_flag equal to 1 specifies that deblocking parameters are present in the PH. ph_deblocking_filter_override_flag equal to 0 specifies that deblocking parameters are not present in the PH. When not present, the value of ph_deblocking_filter_override_flag is inferred to be equal to 0.

ph_deblocking_filter_disabled_flag equal to 1 specifies that the operation of the deblocking filter is not applied for the slices associated with the PH. ph_deblocking_filter_disabled_flag equal to 0 specifies that the operation of the deblocking filter is applied for the slices associated with the PH. When ph_deblocking_filter_disabled_flag is not present, it is inferred to be equal to

pps_deblocking_filter_disabled_flag.

ph_beta_offset_div2 and ph_tc_offset_div2 specify the deblocking parameter offsets for and tC (divided by 2) that are applied to the luma component for the slices associated with the PH. The values of ph_beta_offset_div2 and ph_tc_offset_div2 shall both be in the range of -12 to 12, inclusive. When not present, the values of ph_beta_offset_div2 and ph_tc_offset_div2 are inferred to be equal to pps_beta_offset_div2 and pps_tc_offset_div2, respectively.

ph_cb_beta_offset_div2 and ph_cb_tc_offset_div2 specify the deblocking parameter offsets for and tC (divided by 2) that are applied to the Cb component for the slices associated with the PH. The values of ph_cb_beta_offset_div2 and ph_cb_tc_offset_div2 shall both be in the range of -12 to 12, inclusive. When not present, the values of ph_cb_beta_offset_div2 and ph_cb_tc_offset_div2 are inferred to be equal to pps_cb_beta_offset_div2 and pps_cb_tc_offset_div2, respectively.

ph_cr_beta_offset_div2 and ph_cr_tc_offset_div2 specify the deblocking parameter offsets for and tC (divided by 2) that are applied to the Cr component for the slices associated with the PH. The values of ph_cr_beta_offset_div2 and ph_cr_tc_offset_div2 shall both be in the range of -12 to 12, inclusive. When not present, the values of ph_cr_beta_offset_div2 and ph_cr_tc_offset_div2 are inferred to be equal to pps_cr_beta_offset_div2 and pps_cr_tc_offset_div2, respectively.

ph_extension_length specifies the length of the PH extension data in bytes, not including the bits used for signalling ph_extension_length itself. The value of ph_extension_length shall be in the range of 0 to 256, inclusive. When not present, the value of ph_extension_length is inferred to be equal to 0.

ph_extension_data_byte may have any value. Decoders conforming to this version of this Specification shall ignore the value of ph_extension_data_byte. Its value does not affect decoder conformance to profiles specified in this version of specification.

3.9. SH Syntax and Semantics

In the latest VVC draft text, the SH syntax and semantics are as follows:

```
(62) TABLE-US-00036 Descriptor slice_header( ) {    picture_header_in_slice_header_flag u(1)    if(
picture_header_in_slice_header_flag )        picture_header_structure( )    if( subpic_info_present_flag )
    slice_subpic_id u(v)    if( ( rect_slice_flag && NumSlicesInSubpic[ CurrSubpicIdx ] > 1 ) ||
```

```

    ( !rect_slice_flag && NumTilesInPic > 1 ) ) slice_address u(v) for( i = 0; i <
NumExtraShBits; i++ ) sh_extra_bit[ i ] u(1) if( !rect_slice_flag && NumTilesInPic > 1 )
num_tiles_in_slice_minus1 ue(v) if( ph_inter_slice_allowed_flag ) slice_type ue(v) if(
sps_alf_enabled_flag && !alf_info_in_ph_flag ) { slice_alf_enabled_flag u(1) if(
slice_alf_enabled_flag ) { slice_num_alf_aps_ids_luma u(3) for( i = 0; i <
slice_num_alf_aps_ids_luma; i++ ) slice_alf_aps_id_luma[ i ] u(3) if(
ChromaArrayType != 0 ) slice_alf_chroma_idc u(2) if( slice_alf_chroma_idc )
slice_alf_aps_id_chroma u(3) if( sps_ccalf_enabled_flag ) {
slice_cc_alf_cb_enabled_flag u(1) if( slice_cc_alf_cb_enabled_flag )
slice_cc_alf_cb_aps_id u(3) slice_cc_alf_cr_enabled_flag u(1) if(
slice_cc_alf_cr_enabled_flag ) slice_cc_alf_cr_aps_id u(3) } } } if(
separate_colour_plane_flag == 1 ) colour_plane_id u(2) if( !rpl_info_in_ph_flag && ( (
nal_unit_type != IDR_W_RADL && nal_unit_type != IDR_N_LP ) || sps_idr_rpl_present_flag ) )
ref_pic_lists( ) if( ( rpl_info_in_ph_flag || ( ( nal_unit_type != IDR_W_RADL && nal_unit_type
!= IDR_N_LP ) || sps_idr_rpl_present_flag ) ) && ( slice_type != I && num_ref_entries[ 0
][ RplsIdx[ 0 ] ] > 1 ) || ( slice_type == B && num_ref_entries[ 1 ][ RplsIdx[ 1 ] ] > 1 ) ) {
num_ref_idx_active_override_flag u(1) if( num_ref_idx_active_override_flag ) for( i = 0; i
< ( slice_type == B ? 2 : 1 ); i++ ) if( num_ref_entries[ i ][ RplsIdx[ i ] ] > 1 )
num_ref_idx_active_minus1[ i ] ue(v) } if( slice_type != I ) { if( cabac_init_present_flag )
cabac_init_flag u(1) if( ph_temporal_mvp_enabled_flag && !rpl_info_in_ph_flag ) {
if( slice_type == B ) slice_collocated_from_l0_flag u(1) if( (
slice_collocated_from_l0_flag && NumRefIdxActive[ 0 ] > 1 ) || ( !
slice_collocated_from_l0_flag && NumRefIdxActive[ 1 ] > 1 ) ) slice_collocated_ref_idx ue(v)
} if( !wp_info_in_ph_flag && ( ( pps_weighted_pred_flag && slice_type == P ) || (
pps_weighted_bipred_flag && slice_type == B ) ) ) pred_weight_table( ) } if(
!qp_delta_info_in_ph_flag ) slice_qp_delta se(v) if( pps_slice_chroma_qp_offsets_present_flag ) {
slice_cb_qp_offset se(v) slice_cr_qp_offset se(v) if( sps_joint_cbr_enabled_flag )
slice_joint_cbr_qp_offset se(v) } if( pps_cu_chroma_qp_offset_list_enabled_flag )
cu_chroma_qp_offset_enabled_flag u(1) if( sps_sao_enabled_flag && !sao_info_in_ph_flag ) {
slice_sao_luma_flag u(1) if( ChromaArrayType != 0 ) slice_sao_chroma_flag u(1) }
if( deblocking_filter_override_enabled_flag && !dbf_info_in_ph_flag )
slice_deblocking_filter_override_flag u(1) if( slice_deblocking_filter_override_flag ) {
slice_deblocking_filter_disabled_flag u(1) if( !slice_deblocking_filter_disabled_flag ) {
slice_beta_offset_div2 se(v) slice_tc_offset_div2 se(v) slice_cb_beta_offset_div2 se(v)
slice_cb_tc_offset_div2 se(v) slice_cr_beta_offset_div2 se(v)
slice_cr_tc_offset_div2 se(v) } } slice_ts_residual_coding_disabled_flag u(1) if(
ph_lmcs_enabled_flag ) slice_lmcs_enabled_flag u(1) if( ph_scaling_list_enabled_flag )
slice_scaling_list_present_flag u(1) if( NumEntryPoints > 0 ) { offset_len_minus1 ue(v) for(
i = 0; i < NumEntryPoints; i++ ) entry_point_offset_minus1[ i ] u(v) } if(
slice_header_extension_present_flag ) { slice_header_extension_length ue(v) for( i = 0; i <
slice_header_extension_length; i++ ) slice_header_extension_data_byte[ i ] u(8) }
byte_alignment( ) }

```

The variable `CuQpDeltaVal`, specifying the difference between a luma quantization parameter for the coding unit containing `cu_qp_delta_abs` and its prediction, is set equal to 0. The variables `CuQpOffset.sub.Cb`, `CuQpOffset.sub.Cr`, and `CuQpOffset.sub.CbCr`, specifying values to be used when determining the respective values of the `Qp'.sub.Cb`, `Qp'.sub.Cr`, and `Qp'.sub.CbCr`, quantization parameters for the coding unit containing `cu_chroma_qp_offset_flag`, are all set equal to 0. `picture_header_in_slice_header_flag` equal to 1 specifies that the PH syntax structure is present in the slice header. `picture_header_in_slice_header_flag` equal to 0 specifies that the PH syntax structure is not present in the slice header. It is a requirement of bitstream conformance that the value of `picture_header_in_slice_header_flag` shall be the same in all coded slices in a CLVS. When `picture_header_in_slice_header_flag` is equal to 1 for a coded slice, it is a requirement of bitstream conformance that no VCL NAL unit with `nal_unit_type` equal to `PH_NUT` shall be present in the CLVS.

When picture_header_in_slice_header_flag is equal to 0, all coded slices in the current picture shall have picture_header_in_slice_header_flag is equal to 0, and the current PU shall have a PH NAL unit. slice_subpic_id specifies the subpicture ID of the subpicture that contains the slice. If slice_subpic_id is present, the value of the variable CurrSubpicIdx is derived to be such that SubpicIdVal[CurrSubpicIdx] is equal to slice_subpic_id. Otherwise (slice_subpic_id is not present), CurrSubpicIdx is derived to be equal to 0. The length of slice_subpic_id is sps_subpic_id_len_minus1+1 bits.

slice_address specifies the slice address of the slice. When not present, the value of slice_address is inferred to be equal to 0. When rect_slice_flag is equal to 1 and NumSlicesInSubpic[CurrSubpicIdx] is equal to 1, the value of slice_address is inferred to be equal to 0.

If rect_slice_flag is equal to 0, the following applies: The slice address is the raster scan tile index. The length of slice_address is $\text{Ceil}(\text{Log}_2(\text{NumTilesInPic}))$ bits. The value of slice_address shall be in the range of 0 to NumTilesInPic-1, inclusive.

Otherwise (rect_slice_flag is equal to 1), the following applies: The slice address is the subpicture-level slice index of the slice. The length of slice_address is $\text{Ceil}(\text{Log}_2(\text{NumSlicesInSubpic}[\text{CurrSubpicIdx}]))$ bits. The value of slice_address shall be in the range of 0 to NumSlicesInSubpic[CurrSubpicIdx]-1, inclusive.

(63) It is a requirement of bitstream conformance that the following constraints apply: If rect_slice_flag is equal to 0 or subpic_info_present_flag is equal to 0, the value of slice_address shall not be equal to the value of slice_address of any other coded slice NAL unit of the same coded picture. Otherwise, the pair of slice_subpic_id and slice_address values shall not be equal to the pair of slice_subpic_id and slice_address values of any other coded slice NAL unit of the same coded picture. The shapes of the slices of a picture shall be such that each CTU, when decoded, shall have its entire left boundary and entire top boundary consisting of a picture boundary or consisting of boundaries of previously decoded CTU(s).

sh_extra_bit[i] may be equal to 1 or 0. Decoders conforming to this version of this Specification shall ignore the value of sh_extra_bit[i]. Its value does not affect decoder conformance to profiles specified in this version of specification.

num_tiles_in_slice_minus1 plus 1, when present, specifies the number of tiles in the slice. The value of num_tiles_in_slice_minus1 shall be in the range of 0 to NumTilesInPic-1, inclusive.

The variable NumCtusInCurrSlice, which specifies the number of CTUs in the current slice, and the list CtbAddrInCurrSlice[i], for i ranging from 0 to NumCtusInCurrSlice-1, inclusive, specifying the picture raster scan address of the i-th CTB within the slice, are derived as follows:

```
(64) TABLE-US-00037 if( rect_slice_flag ) {   picLevelSliceIdx = slice_address   for( j = 0; j <
CurrSubpicIdx; j++ )   picLevelSliceIdx += NumSlicesInSubpic[ j ]   NumCtusInCurrSlice =
NumCtusInSlice[ picLevelSliceIdx ]   for( i = 0; i < NumCtusInCurrSlice; i++ )
CtbAddrInCurrSlice[ i ] = CtbAddrInSlice[ (117)   picLevelSliceIdx ][ i ]   } else {
NumCtusInCurrSlice = 0   for( tileIdx = slice_address; tileIdx <= slice_address +
num_tiles_in_slice_minus1; tileIdx++ ) {       tileX = tileIdx % NumTileColumns       tileY = tileIdx /
NumTileColumns       for( ctbY = tileRowBd[ tileY ]; ctbY < tileRowBd[ tileY + 1 ];       ctbY++ ) {
for( ctbX = tileColBd[ tileX ]; ctbX < tileColBd[ tileX + 1 ];       ctbX++ ) {
CtbAddrInCurrSlice[ NumCtusInCurrSlice ] = ctbY *       PicWidthInCtb + ctbX
NumCtusInCurrSlice++       }       }   } }
```

The variables SubpicLeftBoundaryPos, SubpicTopBoundaryPos, SubpicRightBoundaryPos, and SubpicBotBoundaryPos are derived as follows:

```
(65) TABLE-US-00038 if( subpic_treated_as_pic_flag[ CurrSubpicIdx ] ) {   SubpicLeftBoundaryPos =
subpic_ctu_top_left_x[ CurrSubpicIdx ] * CtbSizeY   SubpicRightBoundaryPos = Min(
pic_width_max_in_luma_samples - 1,   ( subpic_ctu_top_left_x[ CurrSubpicIdx ] +
subpic_width_minus1[ CurrSubpicIdx ] + 1 ) * CtbSizeY - 1 )   SubpicTopBoundaryPos =
subpic_ctu_top_left_y[ (118)   CurrSubpicIdx ] * CtbSizeY   SubpicBotBoundaryPos = Min(
pic_height_max_in_luma_samples - 1,   ( subpic_ctu_top_left_y[ CurrSubpicIdx ] +
subpic_height_minus1[ CurrSubpicIdx ] + 1 ) * CtbSizeY - 1 ) }
```

slice_type specifies the coding type of the slice according to Table 9.

(66) TABLE-US-00039 TABLE 9 Name association to slice_type slice_type Name of slice_type 0 B (B slice) 1 P (P slice) 2 I (I slice)

When not present, the value of slice_type is inferred to be equal to 2.

When ph_intra_slice_allowed_flag is equal to 0, the value of slice_type shall be equal to 0 or 1. When nal_unit_type is in the range of IDR_W_RADL to CRA_NUT, inclusive, and vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]] is equal to 1, slice_type shall be equal to 2. The variables MinQtLog2SizeY, MinQtLog2SizeC, MinQtSizeY, MinQtSizeC, MaxBtSizeY, MaxBtSizeC, MinBtSizeY, MaxTtSizeY, MaxTtSizeC, MinTtSizeY, MaxMttDepthY and MaxMttDepthC are derived as follows: If slice_type equal to 2 (I), the following applies:

$$\text{MinQtLog2SizeY} = \text{MinCbLog2SizeY} + \text{ph_log2_diff_min_qt_min_cb_intra_slice_luma} \quad (119)$$

$$\text{MinQtLog2SizeC} = \text{MinCbLog2SizeY} + \text{ph_log2_diff_min_qt_min_cb_intra_slice_chroma} \quad (120)$$

$$\text{MaxBtSizeY} = 1 \ll (\text{MinQtLog2SizeY} + \text{ph_log2_diff_max_bt_min_qt_intra_slice_luma}) \quad (121)$$

$$\text{MaxBtSizeC} = 1 \ll (\text{MinQtLog2SizeC} + \text{ph_log2_diff_max_bt_min_qt_intra_slice_chroma}) \quad (122)$$

$$\text{MaxTtSizeY} = 1 \ll (\text{MinQtLog2SizeY} + \text{ph_log2_diff_max_tt_min_qt_intra_slice_luma}) \quad (123)$$

$$\text{MaxTtSizeC} = 1 \ll (\text{MinQtLog2SizeC} + \text{ph_log2_diff_max_tt_min_qt_intra_slice_chroma}) \quad (124)$$

$$\text{MaxMttDepthY} = \text{ph_max_mtt_hierarchy_depth_intra_slice_luma} \quad (125)$$

$$\text{MaxMttDepthC} = \text{ph_max_mtt_hierarchy_depth_intra_slice_chroma} \quad (126)$$

$$\text{CuQpDeltaSubdiv} = \text{ph_cu_qp_delta_subdiv_intra_slice} \quad (127)$$

CuChromaQpOffsetSubdiv=ph_cu_chroma_qp_offset_subdiv_intra_slice (128) Otherwise (slice_type equal to 0 (B) or 1 (P)), the following applies:

$$\text{MinQtLog2SizeY} = \text{MinCbLog2SizeY} + \text{ph_log2_diff_min_qt_min_cb_inter_slice} \quad (129)$$

$$\text{MinQtLog2SizeC} = \text{MinCbLog2SizeY} + \text{ph_log2_diff_min_qt_min_cb_inter_slice} \quad (130)$$

$$\text{MaxBtSizeY} = 1 \ll (\text{MinQtLog2SizeY} + \text{ph_log2_diff_max_bt_min_qt_inter_slice}) \quad (131)$$

$$\text{MaxBtSizeC} = 1 \ll (\text{MinQtLog2SizeC} + \text{ph_log2_diff_max_bt_min_qt_inter_slice}) \quad (132)$$

$$\text{MaxTtSizeY} = 1 \ll (\text{MinQtLog2SizeY} + \text{ph_log2_diff_max_tt_min_qt_inter_slice}) \quad (133)$$

$$\text{MaxTtSizeC} = 1 \ll (\text{MinQtLog2SizeC} + \text{ph_log2_diff_max_tt_min_qt_inter_slice}) \quad (134)$$

$$\text{MaxMttDepthY} = \text{ph_max_mtt_hierarchy_depth_inter_slice} \quad (135)$$

$$\text{MaxMttDepthC} = \text{ph_max_mtt_hierarchy_depth_inter_slice} \quad (136)$$

$$\text{CuQpDeltaSubdiv} = \text{ph_cu_qp_delta_subdiv_inter_slice} \quad (137)$$

CuChromaQpOffsetSubdiv=ph_cu_chroma_qp_offset_subdiv_inter_slice (138) The following applies:

$$\text{MinQtSizeY} = 1 \ll \text{MinQtLog2SizeY} \quad (139)$$

$$\text{MinQtSizeC} = 1 \ll \text{MinQtLog2SizeC} \quad (140)$$

$$\text{MinBtSizeY} = 1 \ll \text{MinCbLog2SizeY} \quad (141)$$

$$\text{MinTtSizeY} = 1 \ll \text{MinCbLog2SizeY} \quad (142)$$

slice_alf_enabled_flag equal to 1 specifies that adaptive loop filter is enabled and may be applied to Y, Cb, or Cr color component in a slice. slice_alf_enabled_flag equal to 0 specifies that adaptive loop filter is disabled for all color components in a slice. When not present, the value of slice_alf_enabled_flag is inferred to be equal to ph_alf_enabled_flag.

slice_num_alf_aps_ids_luma specifies the number of ALF APSs that the slice refers to. When slice_alf_enabled_flag is equal to 1 and slice_num_alf_aps_ids_luma is not present, the value of slice_num_alf_aps_ids_luma is inferred to be equal to the value of ph_num_alf_aps_ids_luma.

slice_alf_aps_id_luma[i] specifies the adaptation_parameter_set_id of the i-th ALF APS that the luma component of the slice refers to. The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_luma[i] shall be less than or equal to the TemporalId of the coded slice NAL unit. When slice_alf_enabled_flag is equal to 1 and slice_alf_aps_id_luma[i] is not present, the value of slice_alf_aps_id_luma[i] is inferred to be equal to the value of ph_alf_aps_id_luma[i].

The value of alf_luma_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_luma[i] shall be equal to 1.

slice_alf_chroma_idc equal to 0 specifies that the adaptive loop filter is not applied to Cb and Cr color components. slice_alf_chroma_idc equal to 1 indicates that the adaptive loop filter is applied to the Cb color component. slice_alf_chroma_idc equal to 2 indicates that the adaptive loop filter is applied to the Cr color component. slice_alf_chroma_idc equal to 3 indicates that the adaptive loop filter is applied to Cb and Cr color components. When slice_alf_chroma_idc is not present, it is inferred to be equal to

ph_alf_chroma_idc.

slice_alf_aps_id_chroma specifies the adaptation_parameter_set_id of the ALF APS that the chroma component of the slice refers to. The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_chroma shall be less than or equal to the TemporalId of the coded slice NAL unit. When slice_alf_enabled_flag is equal to 1 and slice_alf_aps_id_chroma is not present, the value of slice_alf_aps_id_chroma is inferred to be equal to the value of ph_alf_aps_id_chroma.

The value of alf_chroma_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_chroma shall be equal to 1.

slice_cc_alf_cb_enabled_flag equal to 0 specifies that the cross-component filter is not applied to the Cb color component. slice_cc_alf_cb_enabled_flag equal to 1 indicates that the cross-component filter is enabled and may be applied to the Cb color component. When slice_cc_alf_cb_enabled_flag is not present, it is inferred to be equal to ph_cc_alf_cb_enabled_flag.

slice_cc_alf_cb_aps_id specifies the adaptation_parameter_set_id that the Cb color component of the slice refers to. The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cb_aps_id shall be less than or equal to the TemporalId of the coded slice NAL unit. When slice_cc_alf_cb_enabled_flag is equal to 1 and slice_cc_alf_cb_aps_id is not present, the value of slice_cc_alf_cb_aps_id is inferred to be equal to the value of ph_cc_alf_cb_aps_id.

The value of alf_cc_cb_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cb_aps_id shall be equal to 1.

slice_cc_alf_cr_enabled_flag equal to 0 specifies that the cross-component filter is not applied to the Cr color component. slice_cc_alf_cr_enabled_flag equal to 1 indicates that the cross-component adaptive loop filter is enabled and may be applied to the Cr color component. When slice_cc_alf_cr_enabled_flag is not present, it is inferred to be equal to ph_cc_alf_cr_enabled_flag.

slice_cc_alf_cr_aps_id specifies the adaptation_parameter_set_id that the Cr color component of the slice refers to. The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cr_aps_id shall be less than or equal to the TemporalId of the coded slice NAL unit. When slice_cc_alf_cr_enabled_flag is equal to 1 and slice_cc_alf_cr_aps_id is not present, the value of slice_cc_alf_cr_aps_id is inferred to be equal to the value of ph_cc_alf_cr_aps_id.

The value of alf_cc_cr_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cr_aps_id shall be equal to 1.

colour_plane_id identifies the color plane associated with the current slice when

separate_colour_plane_flag is equal to 1. The value of colour_plane_id shall be in the range of 0 to 2, inclusive. colour_plane_id values 0, 1 and 2 correspond to the Y, Cb and Cr planes, respectively. The value 3 of colour_plane_id is reserved for future use by ITU-T|ISO/IEC. NOTE 1—There is no dependency between the decoding processes of different color planes of one picture.

num_ref_idx_active_override_flag equal to 1 specifies that the syntax element

num_ref_idx_active_minus1[0] is present for P and B slices and the syntax element

num_ref_idx_active_minus1[1] is present for B slices. num_ref_idx_active_override_flag equal to 0

specifies that the syntax elements num_ref_idx_active_minus1[0] and num_ref_idx_active_minus1[1] are not present. When not present, the value of num_ref_idx_active_override_flag is inferred to be equal to 1.

num_ref_idx_active_minus1[i] is used for the derivation of the variable NumRefIdxActive[i] as specified by Equation 143. The value of num_ref_idx_active_minus1[i] shall be in the range of 0 to 14, inclusive.

For i equal to 0 or 1, when the current slice is a B slice, num_ref_idx_active_override_flag is equal to 1, and num_ref_idx_active_minus1[i] is not present, num_ref_idx_active_minus1[i] is inferred to be equal to 0.

When the current slice is a P slice, num_ref_idx_active_override_flag is equal to 1, and

num_ref_idx_active_minus1[0] is not present, num_ref_idx_active_minus1[0] is inferred to be equal to 0.

The variable NumRefIdxActive[i] is derived as follows:

```
(67) TABLE-US-00040 for( i = 0; i < 2; i++ ) {    if( slice_type == B || ( slice_type == P && i == 0 ) )  
{        if( num_ref_idx_active_override_flag )            NumRefIdxActive[ i ] = (143)
```

```

num_ref_idx_active_minus1[ i ] + 1      else {      if( num_ref_entries[ i ][ RplIdx[ i ] ] >=
num_ref_idx_default_active_minus1[ i ] + 1 )      NumRefIdxActive[ i ] =
num_ref_idx_default_active_minus1[ i ] + 1      else      NumRefIdxActive[ i ] =
num_ref_entries[ i ][ RplIdx[ i ] ]      }      } else /* slice_type == I || ( slice_type == P && i == 1 ) */
NumRefIdxActive[ i ] = 0 }

```

The value of NumRefIdxActive[i]–1 specifies the maximum reference index for reference picture list i that may be used to decode the slice. When the value of NumRefIdxActive[i] is equal to 0, no reference index for reference picture list i may be used to decode the slice.

When the current slice is a P slice, the value of NumRefIdxActive[0] shall be greater than 0.

When the current slice is a B slice, both NumRefIdxActive[0] and NumRefIdxActive[1] shall be greater than 0. cabac_init_flag specifies the method for determining the initialization table used in the initialization process for context variables. When cabac_init_flag is not present, it is inferred to be equal to 0.

slice_collocated_from_l0_flag equal to 1 specifies that the collocated picture used for temporal motion vector prediction is derived from reference picture list 0. slice_collocated_from_l0_flag equal to 0 specifies that the collocated picture used for temporal motion vector prediction is derived from reference picture list 1.

When slice_type is equal to B or P, ph_temporal_mvp_enabled_flag is equal to 1, and slice_collocated_from_l0_flag is not present, the following applies: If rpl_info_in_ph_flag is equal to 1, slice_collocated_from_l0_flag is inferred to be equal to ph_collocated_from_l0_flag. Otherwise (rpl_info_in_ph_flag is equal to 0 and slice_type is equal to P), the value of slice_collocated_from_l0_flag is inferred to be equal to 1.

slice_collocated_ref_idx specifies the reference index of the collocated picture used for temporal motion vector prediction.

When slice_type is equal to P or when slice_type is equal to B and slice_collocated_from_l0_flag is equal to 1, slice_collocated_ref_idx refers to an entry in reference picture list 0, and the value of slice_collocated_ref_idx shall be in the range of 0 to NumRefIdxActive[0]–1, inclusive.

When slice_type is equal to B and slice_collocated_from_l0_flag is equal to 0, slice_collocated_ref_idx refers to an entry in reference picture list 1, and the value of slice_collocated_ref_idx shall be in the range of 0 to NumRefIdxActive[1]–1, inclusive.

When slice_collocated_ref_idx is not present, the following applies: If rpl_info_in_ph_flag is equal to 1, the value of slice_collocated_ref_idx is inferred to be equal to ph_collocated_ref_idx. Otherwise (rpl_info_in_ph_flag is equal to 0), the value of slice_collocated_ref_idx is inferred to be equal to 0.

It is a requirement of bitstream conformance that the picture referred to by slice_collocated_ref_idx shall be the same for all slices of a coded picture.

It is a requirement of bitstream conformance that the values of pic_width_in_luma_samples and pic_height_in_luma_samples of the reference picture referred to by slice_collocated_ref_idx shall be equal to the values of pic_width_in_luma_samples and pic_height_in_luma_samples, respectively, of the current picture, and RprConstraintsActive[slice_collocated_from_l0_flag?0:1][slice_collocated_ref_idx] shall be equal to 0. slice_qp_delta specifies the initial value of Qp.sub.Y to be used for the coding blocks in the slice until modified by the value of CuQpDeltaVal in the coding unit layer.

When qp_delta_info_in_ph_flag is equal to 0, the initial value of the Qp.sub.Y quantization parameter for the slice, SliceQp.sub.Y, is derived as follows:

$$\text{SliceQp.sub.Y} = 26 + \text{init_qp_minus26} + \text{slice_qp_delta} \quad (144)$$

The value of SliceQp.sub.Y shall be in the range of –QpBdOffset to +63, inclusive.

When either of the following conditions is true: The value of wp_info_in_ph_flag is equal to 1, pps_weighted_pred_flag is equal to 1, and slice_type is equal to P. The value of wp_info_in_ph_flag is equal to 1, pps_weighted_bipred_flag is equal to 1, and slice_type is equal to B.

the following applies: The value of NumRefIdxActive[0] shall be less than or equal to the value of NumWeightsL0. For each reference picture index RefPicList[0][i] for i in the range of 0 to NumRefIdxActive[0]–1, inclusive, the luma weight, Cb weight, and Cr weight that apply to the reference picture index are LumaWeightL0[i], ChromaWeightL0[0][i], and ChromaWeightL0[1][i], respectively.

When wp_info_in_ph_flag is equal to 1, pps_weighted_bipred_flag is equal to 1, and slice_type is equal

to B, the following applies: The value of NumRefIdxActive[1] shall be less than or equal to the value of NumWeightsL1. For each reference picture index RefPicList[1][i] for i in the range of 0 to NumRefIdxActive[1]-1, inclusive, the luma weight, Cb weight, and Cr weight that apply to the reference picture index are LumaWeightL1 [i], ChromaWeightL1 [0][i], and ChromaWeightL1 [1][i], respectively. slice_cb_qp_offset specifies a difference to be added to the value of pps_cb_qp_offset when determining the value of the Qp'.sub.Cb quantization parameter. The value of slice_cb_qp_offset shall be in the range of -12 to +12, inclusive. When slice_cb_qp_offset is not present, it is inferred to be equal to 0. The value of pps_cb_qp_offset+slice_cb_qp_offset shall be in the range of -12 to +12, inclusive. slice_cr_qp_offset specifies a difference to be added to the value of pps_cr_qp_offset when determining the value of the Qp'Cr quantization parameter. The value of slice_cr_qp_offset shall be in the range of -12 to +12, inclusive. When slice_cr_qp_offset is not present, it is inferred to be equal to 0. The value of pps_cr_qp_offset+slice_cr_qp_offset shall be in the range of -12 to +12, inclusive. slice_joint_cbr_qp_offset specifies a difference to be added to the value of pps_joint_cbr_qp_offset_value when determining the value of the Qp'.sub.CbCr. The value of slice_joint_cbr_qp_offset shall be in the range of -12 to +12, inclusive. When slice_joint_cbr_qp_offset is not present, it is inferred to be equal to 0. The value of pps_joint_cbr_qp_offset_value+slice_joint_cbr_qp_offset shall be in the range of -12 to +12, inclusive. cu_chroma_qp_offset_enabled_flag equal to 1 specifies that the cu_chroma_qp_offset_flag may be present in the transform unit and palette coding syntax. cu_chroma_qp_offset_enabled_flag equal to 0 specifies that the cu_chroma_qp_offset_flag is not present in the transform unit or palette coding syntax. When not present, the value of cu_chroma_qp_offset_enabled_flag is inferred to be equal to 0. slice_sao_luma_flag equal to 1 specifies that SAO is enabled for the luma component in the current slice; slice_sao_luma_flag equal to 0 specifies that SAO is disabled for the luma component in the current slice. When slice_sao_luma_flag is not present, it is inferred to be equal to ph_sao_luma_enabled_flag. slice_sao_chroma_flag equal to 1 specifies that SAO is enabled for the chroma component in the current slice; slice_sao_chroma_flag equal to 0 specifies that SAO is disabled for the chroma component in the current slice. When slice_sao_chroma_flag is not present, it is inferred to be equal to ph_sao_chroma_enabled_flag. slice_deblocking_filter_override_flag equal to 1 specifies that deblocking parameters are present in the slice header. slice_deblocking_filter_override_flag equal to 0 specifies that deblocking parameters are not present in the slice header. When not present, the value of slice_deblocking_filter_override_flag is inferred to be equal to ph_deblocking_filter_override_flag. slice_deblocking_filter_disabled_flag equal to 1 specifies that the operation of the deblocking filter is not applied for the current slice. slice_deblocking_filter_disabled_flag equal to 0 specifies that the operation of the deblocking filter is applied for the current slice. When slice_deblocking_filter_disabled_flag is not present, it is inferred to be equal to ph_deblocking_filter_disabled_flag. slice_beta_offset_div2 and slice_tc_offset_div2 specify the deblocking parameter offsets for and tC (divided by 2) that are applied to the luma component for the current slice. The values of slice_beta_offset_div2 and slice_tc_offset_div2 shall both be in the range of -12 to 12, inclusive. When not present, the values of slice_beta_offset_div2 and slice_tc_offset_div2 are inferred to be equal to ph_beta_offset_div2 and ph_tc_offset_div2, respectively. slice_cb_beta_offset_div2 and slice_cb_tc_offset_div2 specify the deblocking parameter offsets for and tC (divided by 2) that are applied to the Cb component for the current slice. The values of slice_cb_beta_offset_div2 and slice_cb_tc_offset_div2 shall both be in the range of -12 to 12, inclusive. When not present, the values of slice_cb_beta_offset_div2 and slice_cb_tc_offset_div2 are inferred to be equal to ph_cb_beta_offset_div2 and ph_cb_tc_offset_div2, respectively. slice_cr_beta_offset_div2 and slice_cr_tc_offset_div2 specify the deblocking parameter offsets for and tC (divided by 2) that are applied to the Cr component for the current slice. The values of slice_cr_beta_offset_div2 and slice_cr_tc_offset_div2 shall both be in the range of -12 to 12, inclusive. When not present, the values of slice_cr_beta_offset_div2 and slice_cr_tc_offset_div2 are inferred to be equal to ph_cr_beta_offset_div2 and ph_cr_tc_offset_div2, respectively. slice_ts_residual_coding_disabled_flag equal to 1 specifies that the residual_coding() syntax structure is used to parse the residual samples of a transform skip block for the current slice.

slice_ts_residual_coding_disabled_flag equal to 0 specifies that the residual_ts_coding() syntax structure is used to parse the residual samples of a transform skip block for the current slice. When slice_ts_residual_coding_disabled_flag is not present, it is inferred to be equal to 0.

slice_lmcs_enabled_flag equal to 1 specifies that luma mapping with chroma scaling is enabled for the current slice. slice_lmcs_enabled_flag equal to 0 specifies that luma mapping with chroma scaling is not enabled for the current slice. When slice_lmcs_enabled_flag is not present, it is inferred to be equal to 0.

slice_scaling_list_present_flag equal to 1 specifies that the scaling list data used for the current slice is derived based on the scaling list data contained in the referenced scaling list APS with aps_params_type equal to SCALING_APS and adaptation_parameter_set_id equal to ph_scaling_list_aps_id.

slice_scaling_list_present_flag equal to 0 specifies that the scaling list data used for the current picture is the default scaling list data derived specified in clause 7.4.3.21. When not present, the value of slice_scaling_list_present_flag is inferred to be equal to 0.

The variable NumEntryPoints, which specifies the number of entry points in the current slice, is derived as follows:

```
(68) TABLE-US-00041 NumEntryPoints = 0 for( i = 1; i < NumCtusInCurrSlice; i++ ) {   ctbAddrX =
CtbAddrInCurrSlice[ i ] % PicWidthInCtbsY   ctbAddrY = CtbAddrInCurrSlice[ i ] /
PicWidthInCtbsY   (145) prevCtbAddrX = CtbAddrInCurrSlice[ i - 1 ] % PicWidthInCtbsY
prevCtbAddrY = CtbAddrInCurrSlice[ i - 1 ] / PicWidthInCtbsY   if( CtbToTileRowBd[ ctbAddrY ] !=
CtbToTileRowBd[ prevCtbAddrY ] || CtbToTileColBd[ ctbAddrX ] != CtbToTileColBd[
prevCtbAddrX ] || ( ctbAddrY != prevCtbAddrY &&
sps_wpp_entry_point_offsets_present_flag ) )   NumEntryPoints++ }
```

offset_len_minus1 plus 1 specifies the length, in bits, of the entry_point_offset_minus1[i] syntax elements. The value of offset_len_minus1 shall be in the range of 0 to 31, inclusive.

entry_point_offset_minus1[i] plus 1 specifies the i-th entry point offset in bytes, and is represented by offset_len_minus1 plus 1 bits. The slice data that follow the slice header consists of NumEntryPoints+1 subsets, with subset index values ranging from 0 to NumEntryPoints, inclusive. The first byte of the slice data is considered byte 0. When present, emulation prevention bytes that appear in the slice data portion of the coded slice NAL unit are counted as part of the slice data for purposes of subset identification. Subset 0 consists of bytes 0 to entry_point_offset_minus1 [0], inclusive, of the coded slice data, subset k, with k in the range of 1 to NumEntryPoints-1, inclusive, consists of bytes firstByte[k] to lastByte[k], inclusive, of the coded slice data with firstByte[k] and lastByte[k] defined as:

```
(69) TABLE-US-00042 firstByte[ k ] = >K=1( entry_point_offset_minus1 [ n - 1 ] + 1 ) (146) lastByte[ k ]
= firstByte[ k ] + entry_point_offset_minus1 [ k ] (147)
```

The last subset (with subset index equal to NumEntryPoints) consists of the remaining bytes of the coded slice data. When sps_entropy_coding_sync_enabled_flag is equal to 0 and the slice contains one or more complete tiles, each subset shall consist of all coded bits of all CTUs in the slice that are within the same tile, and the number of subsets (i.e., the value of NumEntryPoints+1) shall be equal to the number of tiles in the slice.

When sps_entropy_coding_sync_enabled_flag is equal to 0 and the slice contains a subset of CTU rows from a single tile, the NumEntryPoints shall be 0, and the number of subsets shall be 1. The subset shall consist of all coded bits of all CTUs in the slice.

When sps_entropy_coding_sync_enabled_flag is equal to 1, each subset k with k in the range of 0 to NumEntryPoints, inclusive, shall consist of all coded bits of all CTUs in a CTU row within a tile, and the number of subsets (i.e., the value of NumEntryPoints+1) shall be equal to the total number of tile-specific CTU rows in the slice.

slice_header_extension_length specifies the length of the slice header extension data in bytes, not including the bits used for signalling slice_header_extension_length itself. The value of slice_header_extension_length shall be in the range of 0 to 256, inclusive. When not present, the value of slice_header_extension_length is inferred to be equal to 0.

slice_header_extension_data_byte[i] may have any value. Decoders conforming to this version of this Specification shall ignore the values of all the slice_header_extension_data_byte[i] syntax elements. Its value does not affect decoder conformance to profiles specified in this version of specification.

3.10. Reference Picture Lists Syntax

In the latest VVC draft text, the syntax structure `ref_pic_lists()` and semantics are as follows:

```
(70) TABLE-US-00043 Descriptor ref_pic_lists() { for( i = 0; i < 2; i++ ) { if(
num_ref_pic_lists_in_sps[ i ] > 0 && ( i == 0 || ( i == 1 && rpl1_idx_present_flag ) ) )
    rpl_sps_flag[ i ] u(1) if( rpl_sps_flag[ i ] ) { if( num_ref_pic_lists_in_sps[ i ] > 1 &&
        ( i == 0 || ( i == 1 && rpl1_idx_present_flag ) ) ) rpl_idx[ i ] u(v) } else
    ref_pic_list_struct( i, num_ref_pic_lists_in_sps[ i ] ) for( j = 0; j < NumLtrpEntries[ i ]
[RplsIdx[ i ] ]; j++ ) { if( ltrp_in_header_flag[ i ][ RplsIdx[ i ] ] ) poc_lsb_lt[ i ][ j ]
u(v) delta_poc_msb_present_flag[ i ][ j ] u(1) if( delta_poc_msb_present_flag[ i ][ j ] )
    delta_poc_msb_cycle_lt[ i ][ j ] ue(v) } } }
```

The `ref_pic_lists()` syntax structure may be present in the PH syntax structure or the slice header.

`rpl_sps_flag[i]` equal to 1 specifies that reference picture list `i` in `ref_pic_lists()` is derived based on one of the `ref_pic_list_struct(listIdx, rplsIdx)` syntax structures with `listIdx` equal to `i` in the SPS. `rpl_sps_flag[i]` equal to 0 specifies that reference picture list `i` of the picture is derived based on the `ref_pic_list_struct(listIdx, rplsIdx)` syntax structure with `listIdx` equal to `i` that is directly included in `ref_pic_lists()`.

When `rpl_sps_flag[i]` is not present, the following applies: If `num_ref_pic_lists_in_sps[i]` is equal to 0, the value of `rpl_sps_flag[i]` is inferred to be equal to 0. Otherwise (`num_ref_pic_lists_in_sps[i]` is greater than 0), when `rpl1_idx_present_flag` is equal to 0 and `i` is equal to 1, the value of `rpl_sps_flag[1]` is inferred to be equal to `rpl_sps_flag[0]`.

`rpl_idx[i]` specifies the index, into the list of the `ref_pic_list_struct(listIdx, rplsIdx)` syntax structures with `listIdx` equal to `i` included in the SPS, of the `ref_pic_list_struct(listIdx, rplsIdx)` syntax structure with `listIdx` equal to `i` that is used for derivation of reference picture list `i` of the current picture. The syntax element `rpl_idx[i]` is represented by $\text{Ceil}(\text{Log2}(\text{num_ref_pic_lists_in_sps}[i]))$ bits. When not present, the value of `rpl_idx[i]` is inferred to be equal to 0. The value of `rpl_idx[i]` shall be in the range of 0 to `num_ref_pic_lists_in_sps[i]-1`, inclusive. When `rpl_sps_flag[i]` is equal to 1 and `num_ref_pic_lists_in_sps[i]` is equal to 1, the value of `rpl_idx[i]` is inferred to be equal to 0. When `rpl_sps_flag[i]` is equal to 1 and `rpl1_idx_present_flag` is equal to 0, the value of `rpl_idx[1]` is inferred to be equal to `rpl_idx[0]`.

The variable `RplsIdx[i]` is derived as follows:

$$\text{RplsIdx}[i] = \text{rpl_sps_flag}[i] ? \text{rpl_idx}[i] : \text{num_ref_pic_lists_in_sps}[i] \quad (149)$$

`poc_lsb_lt[i][j]` specifies the value of the picture order count modulo `MaxPicOrderCntLsb` of the `j`-th LTRP entry in the `i`-th reference picture list in the `ref_pic_lists()` syntax structure. The length of the `poc_lsb_lt[i][j]` syntax element is $\text{log2_max_pic_order_cnt_lsb_minus4}+4$ bits.

The variable `PocLsbLt[i][j]` is derived as follows:

(71) TABLE-US-00044
$$\text{PocLsbLt}[i][j] = \text{ltrp_in_header_flag}[i][\text{RplsIdx}[i]] ? (150) \text{poc_lsb_lt}[i][j] : \text{rpls_poc_lsb_lt}[\text{listIdx}][\text{RplsIdx}[i]][j]$$

`delta_poc_msb_present_flag[i][j]` equal to 1 specifies that `delta_poc_msb_cycle_lt[i][j]` is present.

`delta_poc_msb_present_flag[i][j]` equal to 0 specifies that `delta_poc_msb_cycle_lt[i][j]` is not present.

Let `prevTid0Pic` be the previous picture in decoding order that has `nuh_layer_id` the same as the slice or picture header referring to the `ref_pic_lists()` syntax structure, has `TemporalId` equal to 0, and is not a RASL or RADL picture. Let `setOfPrevPocVals` be a set consisting of the following: the `PicOrderCntVal` of `prevTid0Pic`, the `PicOrderCntVal` of each picture that is referred to by entries in `RefPicList[0]` or `RefPicList[1]` of `prevTid0Pic` and has `nuh_layer_id` the same as the current picture, the `PicOrderCntVal` of each picture that follows `prevTid0Pic` in decoding order, has `nuh_layer_id` the same as the current picture, and precedes the current picture in decoding order.

When there is more than one value in `setOfPrevPocVals` for which the value modulo `MaxPicOrderCntLsb` is equal to `PocLsbLt[i][j]`, the value of `delta_poc_msb_present_flag[i][j]` shall be equal to 1.

`delta_poc_msb_cycle_lt[i][j]` specifies the value of the variable `FullPocLt[i][j]` as follows:

(72) TABLE-US-00045
$$\text{if}(j = 0) \quad \text{deltaPocMsbCycleLt}[i][j] = \text{delta_poc_msb_cycle_lt}[i][j] \text{ else}$$

(151)
$$\text{deltaPocMsbCycleLt}[i][j] = \text{delta_poc_msb_cycle_lt}[i][j] + \text{deltaPocMsbCycleLt}[i][j - 1] \text{ FullPocLt}[i][j] = \text{PicOrderCntVal} - \text{deltaPocMsbCycleLt}[i][j] * \text{MaxPicOrderCntLsb} - (\text{PicOrderCntVal} \& (\text{MaxPicOrderCntLsb} - 1)) + \text{PocLsbLt}[i][j]$$

The value of `delta_poc_msb_cycle_lt[i][j]` shall be in the range of 0 to 2.sup.

(32-log2_max_pic_order_cnt_lsb_minus4), inclusive. When not present, the value of delta_poc_msb_cycle_lt[i][j] is inferred to be equal to 0.

3.11. Reference Picture List Structure Syntax

In the latest VVC draft text, the syntax structure ref_pic_lists() and semantics are as follows:

(73) TABLE-US-00046 Descriptor ref_pic_list_struct(listIdx, rplIdx) { **num_ref_entries**[listIdx][rplIdx] ue(v) if(long_term_ref_pics_flag) **ltrp_in_header_flag**[listIdx][rplIdx] u(1) for(i = 0, j = 0; i < num_ref_entries[listIdx][rplIdx]; i++) { if(inter_layer_ref_pics_present_flag) **inter_layer_ref_pic_flag**[listIdx][rplIdx][i] u(1) if(!inter_layer_ref_pic_flag[listIdx][rplIdx][i]) { if(long_term_ref_pics_flag) **st_ref_pic_flag**[listIdx][rplIdx][i] u(1) if(st_ref_pic_flag[listIdx][rplIdx][i]) { **abs_delta_poc_st**[listIdx][rplIdx][i] ue(v) if(AbsDeltaPocSt[listIdx][rplIdx][i] > 0) **strp_entry_sign_flag**[listIdx][rplIdx][i] u(1) } else if(!ltrp_in_header_flag[listIdx][rplIdx]) **rpls_poc_lsb_lt**[listIdx][rplIdx][j++] u(v) } else **ilrp_idx**[listIdx][rplIdx][i] ue(v) } }

The ref_pic_list_struct(listIdx, rplIdx) syntax structure may be present in an SPS, in a PH syntax structure, or in a slice header. Depending on whether the syntax structure is included in an SPS, a PH syntax structure, or a slice header, the following applies: If present in a PH syntax structure or a slice header, the ref_pic_list_struct(listIdx, rplIdx) syntax structure specifies reference picture list listIdx of the current picture (the picture containing the slice). Otherwise (present in an SPS), the

ref_pic_list_struct(listIdx, rplIdx) syntax structure specifies a candidate for reference picture list listIdx, and the term “the current picture” in the semantics specified in the remainder of this clause refers to each picture that 1) has a PH syntax structure containing ph_rpl_idx[listIdx] equal to an index into the list of the ref_pic_list_struct(listIdx, rplIdx) syntax structures included in the SPS or one or more slices containing slice_rpl_idx[listIdx] equal to an index into the list of the ref_pic_list_struct(listIdx, rplIdx) syntax structures included in the SPS, and 2) is in a CVS that refers to the SPS.

num_ref_entries[listIdx][rplIdx] specifies the number of entries in the ref_pic_list_struct(listIdx, rplIdx) syntax structure. The value of num_ref_entries[listIdx][rplIdx] shall be in the range of 0 to MaxDpbSize+13, inclusive, where MaxDpbSize is as specified in clause A.4.2.

ltrp_in_header_flag[listIdx][rplIdx] equal to 0 specifies that the POC LSBs of the LTRP entries in the ref_pic_list_struct(listIdx, rplIdx) syntax structure are present in the ref_pic_list_struct(listIdx, rplIdx) syntax structure. ltrp_in_header_flag[listIdx][rplIdx] equal to 1 specifies that the POC LSBs of the LTRP entries in the ref_pic_list_struct(listIdx, rplIdx) syntax structure are not present in the ref_pic_list_struct(listIdx, rplIdx) syntax structure.

inter_layer_ref_pic_flag[listIdx][rplIdx][i] equal to 1 specifies that the i-th entry in the ref_pic_list_struct(listIdx, rplIdx) syntax structure is an ILRP entry. inter_layer_ref_pic_flag[listIdx][rplIdx][i] equal to 0 specifies that the i-th entry in the ref_pic_list_struct(listIdx, rplIdx) syntax structure is not an ILRP entry. When not present, the value of inter_layer_ref_pic_flag[listIdx][rplIdx][i] is inferred to be equal to 0.

st_ref_pic_flag[listIdx][rplIdx][i] equal to 1 specifies that the i-th entry in the ref_pic_list_struct(listIdx, rplIdx) syntax structure is an STRP entry. st_ref_pic_flag[listIdx][rplIdx][i] equal to 0 specifies that the i-th entry in the ref_pic_list_struct(listIdx, rplIdx) syntax structure is an LTRP entry. When inter_layer_ref_pic_flag[listIdx][rplIdx][i] is equal to 0 and st_ref_pic_flag[listIdx][rplIdx][i] is not present, the value of st_ref_pic_flag[listIdx][rplIdx][i] is inferred to be equal to 1.

The variable NumLtrpEntries[listIdx][rplIdx] is derived as follows:

(74) TABLE-US-00047 for(i = 0, NumLtrpEntries[listIdx][rplIdx] = 0; i < num_ref_entries[listIdx][rplIdx]; i++) if(!inter_layer_ref_pic_flag[listIdx][rplIdx][i] && !st_ref_pic_flag[listIdx][rplIdx][i]) (152) NumLtrpEntries[listIdx][rplIdx]++

abs_delta_poc_st[listIdx][rplIdx][i] specifies the value of the variable AbsDeltaPocSt[listIdx][rplIdx][i] as follows:

(75) TABLE-US-00048 if((sps_weighted_pred_flag || sps_weighted_bipred_flag) && i != 0) AbsDeltaPocSt[listIdx][rplIdx][i] = abs_delta_poc_st[(153) listIdx][rplIdx][i] else AbsDeltaPocSt[listIdx][rplIdx][i] = abs_delta_poc_st[listIdx][rplIdx][i] + 1

(76) The value of abs_delta_poc_st[listIdx][rplIdx][i] shall be in the range of 0 to 2.sup.15-1, inclusive.

(77) strp_entry_sign_flag[listIdx][rplIdx][i] equal to 1 specifies that i-th entry in the syntax structure

ref_pic_list_struct(listIdx, rplsIdx) has a value greater than or equal to 0. strp_entry_sign_flag[listIdx][rplsIdx][i] equal to 0 specifies that the i-th entry in the syntax structure ref_pic_list_struct(listIdx, rplsIdx) has a value less than 0. When not present, the value of strp_entry_sign_flag[listIdx][rplsIdx][i] is inferred to be equal to 1.

The list DeltaPocValSt[listIdx][rplsIdx] is derived as follows:

(78) TABLE-US-00049 for (i = 0; i < num_ref_entries[listIdx][rplsIdx]; i++) if(!inter_layer_ref_pic_flag[listIdx][rplsIdx][i] && st_ref_pic_flag[listIdx][rplsIdx][i]) (154)

DeltaPocValSt[listIdx][rplsIdx][i] = (strp_entry_sign_flag[listIdx][rplsIdx][i]) ?

AbsDeltaPocSt[listIdx][rplsIdx][i] : 0 - AbsDeltaPocSt[listIdx][rplsIdx][i]

rpls_poc_lsb_lt[listIdx][rplsIdx][i] specifies the value of the picture order count modulo MaxPicOrderCntLsb of the picture referred to by the i-th entry in the ref_pic_list_struct(listIdx, rplsIdx) syntax structure. The length of the rpls_poc_lsb_lt[listIdx][rplsIdx][i] syntax element is log2_max_pic_order_cnt_lsb_minus4+4 bits.

ilrp_idx[listIdx][rplsIdx][i] specifies the index, to the list of the direct reference layers, of the ILRP of the i-th entry in the ref_pic_list_struct(listIdx, rplsIdx) syntax structure. The value of ilrp_idx[listIdx][rplsIdx][i] shall be in the range of 0 to NumDirectRefLayers[GeneralLayerIdx[nuh_layer_id]]-1, inclusive.

4. Examples of Technical Problems Solved by Disclosed Techniques

(79) The existing designs for constraint flags have the following problems:

(80) 1) Currently, whenever there is a PTL syntax structure with profileTierPresentFlag equal to 1, all the general constraint flags/fields are signalled in that PTL syntax structure (SS). Considering that PTL syntax structures may be included in DCI (one or more times, each time with profileTierPresentFlag equal to 1), in VPS (one or more times, the first time with profileTierPresentFlag equal to 1, other times with profileTierPresentFlag equal to either 0 or 1), and in SPS (zero or one time, with profileTierPresentFlag equal to 1), potentially there can be lots of redundant signalling of the general constraint flags/fields. Furthermore, it is possible that none of the general constraints may apply while in this case at least one set of general constraint flags/fields is still signalled for the bitstream of each OLS. 2) In the latest VVC draft text, the general constraint flags are used to constrain the values of some SPS/PH/SH syntax elements (SEs) or their combinations via bitstream constraint in the semantics. However, they can also be used to condition the presence of such related SPS/PH/SH SEs, which would allow skipping the signalling of bits for which their values are known thus avoiding waste of bits. a. In the general_constraint_info() syntax in the latest VVC draft text, the syntax elements such as no_aps_constraint_flag affect a group of techniques such as ALF, CCALF, LMCS, scaling list, and etc. However, the current design does not cover all cases (e.g., in terms of specifying constraints on values of related syntax elements or conditioning the presence of related syntax elements). 3) In the latest VVC draft text, some PPS SEs that relate to general constraint flags can only have certain values depending on values of certain general constraint flags. However, some semantics constraints are missing to disallow illegal values of such PPS SEs. 4) In the general_constraint_info() syntax in the latest VVC draft text, a bunch of general constraint flags have interactions with each other, i.e., certain values of general constraint flags depend the values of other general constraint flags. However, there lacks constraints to disallow illegal values of such general constraint flags, by either bitstream constraints or syntax conditioning. 5) Some syntax elements may be added to SPS and/or PPS to condition the presences of some SPS/PPS/PH/SH syntax elements for saving bits. 6) In the general_constraint_info() syntax in the latest VVC draft text, constraint flags for a subset of coding tools and functionalities are included. However, there are other coding tools (e.g., wavefront parallel processing (WPP), entropy coding sync, weighted prediction, weighted bi-prediction, symmetric motion vector (MV) difference (SMVD), merge with MV difference (MMVD), intra sub-partitions (ISP), multiple reference line (MRL), matrix-based intra prediction (MIP), low-frequency non-separable transform (LFNST), Palette, adaptive color transform (ACT), scaling list, etc.) and functionalities (e.g., single layer only, one sub-picture only, no inter-layer prediction, no virtual boundaries, no long term reference, no 32×32 max luma transform size, no merge estimation region (MER), and etc.) that do not have corresponding constraint flags. 7) In the latest VVC draft text, APS s do not refer to a PPS, an SPS, or a VPS. However, the semantics of some APS SEs depends on values of SEs of VPS, SPS, or PPS. Either all such dependencies should be removed or an PPS or SPS or VPS ID is added to the APS syntax to allow the referencing of PPS or SPS or VPS thus allowing such semantics dependencies. 8) Once the

associated information of a feature can be signalled either in the PH or SH, there might be a flag (named `X_info_in_ph_flag`) signalled in the PPS to specify whether they are going to be signalled in the PH or SH. Right now, in the VVC spec, the flag `X_info_in_ph_flag` is always signalled in the PPS, without any condition. However, if there is only one slice in the picture, there is no need to signal this `X_info_in_ph_flag` in the PPS. It is proposed to conditional signal the PPS flag `X_info_in_ph_flag` (any existing features or potential features in the future) based on the already known picture partition flag in the bitstream (e.g., `no_pic_partition_flag` in the PPS).

9) Currently, the values of some APS syntax elements are constrained based on `ChromaArrayType` derived from SPS syntax elements `chroma_format_idc` and `separate_colour_plane_flag`. However, this would cause semantics dependency since there is no PPS/SPS ID in the APS syntax structure. Therefore, this semantics dependency of APS on SPS should not occur.

10) Currently, the GCI syntax structure would be signalled as long as the `profileTierPresentFlag` associated with `profile_tier_level()` syntax structure is equal to 1. In such case, multiple GCI syntax structures with different content may be signalled for a same profile ID, which may be confused and not efficient. a. Moreover, the reserved GCI syntax elements are counted by bytes, which may not be desirable.

11) Currently, the general constraints information (GCI) syntax structure would be signalled as long as the `profileTierPresentFlag` associated with `profile_tier_level()` syntax structure is equal to 1. In such case, multiple GCI syntax structures with different content may be signalled for a same profile ID, which may be confused and not efficient. a. The RPL related SEs and some GCI SEs are not constrained by the value of `intra_only_constraint_flag`. b. The SEs in the SPS/PPS/PH/SH are not completely constrained by the GCI SEs, e.g., the partition/tile/slice related SEs in the SPS/PPS/PH/SH are not constrained by the value of `one_tile_per_pic_constraint_flag`, and/or `one_slice_per_pic_constraint_flag`. c. `sps_ccalf_enabled_flag`, `ph_num_alf_aps_ids_luma`, `slice_num_alf_aps_ids_luma`, `ph_alf_cb_flag`, `ph_alf_cr_flag`, `sh_alf_cb_flag`, and `sh_alf_cr_flag` should be constrained by the value of `no_aps_constraint_flag`. d. Some GCI SEs may need to be constrained by other GCI SEs, e.g., the inter layer SEs are not constrained by the value of `all_layers_independent_constraint_flag`, and `no_bdpcm_constraint_flag` is not constrained by the value of `no_transform_skip_constraint_flag`. e. The definition of `intra_only_constraint_flag` may need to consider the `nuh_layer_type` for each coded slice NAL unit.

12) Currently, an `aps_chroma_present_flag` is signalled in the APS syntax structure and used to condition the signalling of the chroma scaling list SEs in the `scaling_list_data()` syntax structure. The `aps_chroma_present_flag` is required to be equal to 1 for non-4:0:0 and non-separate-color-plane (e.g., `ChromaArrayType` equal to 1) coding. However, the `aps_chroma_present_flag` could also be equal to 0 for `ChromaArrayType` equal to 1 coding. a. Moreover, currently the scaling list APS ID is signalled for both luma and chroma, which may not be efficient.

5. Example Embodiments

(81) To solve the above problems and some other problems not mentioned, methods as summarized below are disclosed. The embodiments should be considered as examples to explain the general concepts and should not be interpreted in a narrow way. Furthermore, these embodiments can be applied individually or combined in any manner.

1. Regarding the signalling of general constraint flags/fields in general for solving the first problem, one or more of the following approaches are disclosed:

1) A presence flag may be added to the PTL syntax structure to specify whether the `general_constraint_info()` syntax structure is present in the PTL syntax structure. a. In one example, when no `general_constraint_info()` syntax structure is present for an OLS, a default value is inferred for each of the general constraint flags/fields. i. In one example, when no `general_constraint_info()` syntax structure is present for an OLS, each of the general constraint flags/fields is inferred to be a value that specifies that no particular constraint is imposed for the bitstream of the OLS. For example, the values of `intra_only_constraint_flag`, `no_res_change_in_clvs_constraint_flag`, and `one_tile_per_pic_constraint_flag` are all inferred to be equal to 0. b. In one example, in the DCI, when there is more than one PTL syntax structure in it, it may be required that at most one of those PTL syntax structures contains a `general_constraint_info()` syntax structure, and when present, that `general_constraint_info()` syntax structure applies to the entire bitstream. i. Furthermore, it may be required that only the first PTL syntax structure in the DCI may contain a `general_constraint_info()` syntax structure, and the general constraints information associated with the first DCI PTL syntax structure in the DCI (explicitly signalled or inferred) is considered as the general constraints information associated with the DCI, which applies to the entire bitstream. c. In one example,

when a DCI is present in the bitstream, it may be required that no PTL syntax structure present in a VPS or SPS shall contain a `general_constraint_info()` syntax structure, and the general constraints information associated with the DCI (explicitly signalled or inferred) applies to each OLS in each CVS in the bitstream. i. Alternatively, when a DCI is present in the bitstream, it may be required that no PTL syntax structure present in a VPS shall contain a `general_constraint_info()` syntax structure, and the general constraints information associated with the DCI (explicitly signalled or inferred) applies to each OLS containing more than one layer in each CVS in the bitstream. d. In one example, in a VPS, when there is more than one PTL syntax structure in it, it may be required that only one of those PTL syntax structures may contain a `general_constraint_info()` syntax structure, and that `general_constraint_info()` syntax structure applies to each OLS of each CVS in the bitstream. i. Alternatively, in a VPS, when there is more than one PTL syntax structure in it, it may be required that only the first PTL syntax structure in the VPS may contain a `general_constraint_info()` syntax structure, and the general constraints information associated with the first PTL syntax structure (explicitly signalled or inferred) applies to each OLS of each CVS in the bitstream. e. In one example, when there is more than one PTL (and/or `general_constraint_info()` syntax structure signalled in DCI and/or SPS and/or VPS, those PTL (and/or `general_constraint_info()` syntax structures must have the same content in a conformance bitstream. i. In one example, when there is more than one PTL (and/or `general_constraint_info()` syntax structure signalled for an OLS, those PTL (and/or `general_constraint_info()` syntax structures must have the same content in a conformance bitstream. ii. In one example, when there is more than one PTL (and/or `general_constraint_info()` syntax structure signalled for a CVS, those PTL (and/or `general_constraint_info()` syntax structures must have the same content in a conformance bitstream. f. In one example, at most one PTL (and/or `general_constraint_info()` syntax structure is allowed to be signalled in DCI and/or SPS and/or VPS in a conformance bitstream. i. In one example, at most one PTL (and/or `general_constraint_info()` syntax structure is allowed to be signalled for an OLS in a conformance bitstream. ii. In one example, at most one PTL (and/or `general_constraint_info()` syntax structure is allowed to be signalled for a CVS in a conformance bitstream. g. In one example, when there are multiple PTL syntax structures signalled in DCI targeting for multiple OLSs, a syntax element may be added to the DCI syntax structure to specify the index, to the list of PTL syntax structures in the DCI, of the PTL syntax structure that applies to the i-th OLS. i. Additionally, if there is only one OLS in a bitstream, the signalling of the above-mentioned syntax element may be skipped and/or the value of the syntax element is inferred to a certain value (such as 0). h. In one example, when there are multiple `general_constraint_info()` syntax structures in DCI and/or SPS and/or VPS, and the values for a particular general constraint flag/field are different for an OLS, then as long as anyone of the general constraint flags imposes a particular constraint, the particular constraint would be applied to this OLS. i. In one example, when any of the general constraint flags in VPS/SPS specify that a particular constraint is imposed for an OLS, whereas the corresponding general constraint flag in DCI specifies that a particular constraint is not imposed for an OLS, then that OLS may conform to the tighter constraint (e.g., impose such particular constraint to that OLS as indicated in VPS/SPS). 1. Alternatively, when any of the general constraint flags in VPS/SPS specify that a particular constraint is not imposed for an OLS, whereas the corresponding general constraint flag in DCI specifies that a particular constraint is imposed for an OLS, then that OLS may conform to the tighter constraint (e.g., impose such particular constraint to that OLS as indicated in DCI). ii. In one example, for any particular aspect associated with a general constraint syntax element that impose a constraint to an OLS, the corresponding general constraint syntax element carried in DCI has to have a value that indicates a more relaxed than but cannot be tighter than the value of the same constraint regarding that aspect indicated in VPS/SPS. 1. In one example, if any of the general constraint flags/fields in VPS/SPS specify that a particular constraint is not imposed for an OLS, then a bitstream conformance may be added to require that the value of the corresponding general constraint flag in DCI is equal to 0 for that OLS (in this case, the value of the corresponding general constraint flag in DCI cannot be equal to 1). 2. In one example, if any of the general constraint flags/fields in VPS/SPS specify that a particular constraint is imposed for an OLS, then the value of the corresponding general constraint flag in DCI may be equal to 0 or 1 for that OLS. iii. Alternatively, oppositely, for any particular aspect associated with a general constraint syntax element that impose a constraint to an OLS, the corresponding general constraint syntax element carried in DCI has to have a value that indicates a tighter

than but cannot be more relaxed than the value of the same constraint regarding that aspect indicated in VPS/SPS.

1. In one example, if any of the general constraint flags/fields in VPS/SPS specify that a particular constraint is imposed for an OLS, then a bitstream conformance may be added to require that the value of the corresponding general constraint flag in DCI is equal to 1 for that OLS (in this case, the value of the corresponding general constraint flag in DCI cannot be equal to 0).
2. In one example, if any of the general constraint flags/fields in VPS/SPS specify that a particular constraint is not imposed for an OLS, then the value of the corresponding general constraint flag in DCI may be equal to 0 or 1 for that OLS.
 - i. In one example, multiple sets of different default values for the general constraint flags/fields may be pre-defined.
 - ii. Alternatively, furthermore, an indication of one set among the multiple sets may be signalled in a DCI/VPS/SPS.
 - iii. Alternatively, only one set is pre-defined.
 - iv. Alternatively, furthermore, one flag may be present in DCI/VPS/SPS to specify whether the one set is used.
 - v. In one example, for one of the multiple sets, each of the general constraint flags/fields is inferred to be a value that specifies that a particular constraint is not imposed for the bitstream of the OLS. For example, the values of `intra_only_constraint_flag`, `no_res_change_in_clvs_constraint_flag`, and `one_tile_per_pic_constraint_flag` are all inferred to be equal to 0.
 - vi. In one example, for one or some of the multiple sets, the value of `max_bitdepth_constraint_idc` may be inferred to be equal to a particular value, e.g., 2.

2. Regarding the signalling of SPS/PH/SH syntax elements based on the general constraint flags for solving the second problem:

- 1) Depending on the values of general constraint flags, the signalling of the corresponding syntax elements in SPS/PH/SH may be skipped, e.g., as in the first embodiment.
 - a. In one example, signalling of some SPS syntax elements may be skipped according to some general constraint flags.
 - i. For example, in case of the value of the general constraint field `max_chroma_format_constraint_idc` is equal to 0, the signalling of the corresponding SPS syntax element `chroma_format_idc` may be skipped.
 - ii. Additionally, furthermore, when `max_chroma_format_constraint_idc` is equal to 0, the value of `chroma_format_idc` is inferred to be equal to 0.
 - iii. For example, in case of the value of the general constraint field `max_bitdepth_constraint_idc` is equal to 0, the signalling of the corresponding SPS syntax element `bit_depth_minus8` may be skipped.
 - iv. Additionally, furthermore, when `max_bitdepth_constraint_idc` is equal to 0, the value of `bit_depth_minus8` is inferred to be equal to 0.
 - v. For example, in case of the value of the general constraint flag `no_aps_constraint_flag` is equal to 1, the signalling of the APS-related SPS syntax elements (such as `sps_lmcs_enabled_flag`, `sps_scaling_list_enabled_flag`, `sps_alf_enabled_flag`, `sps_ccalf_enabled_flag`, and etc.) may be skipped.
 - vi. Additionally, when `no_aps_constraint_flag` is equal to 1, the value of the above-mentioned each of the APS-related SPS syntax elements is inferred to be equal to 0.
 - vii. Alternatively, furthermore, in case of the value of the general constraint flag `no_aps_constraint_flag` is equal to 1, the NAL unit type is disallowed to be equal to `PREFIX_APS_NUT` or `SUFFIX_APS_NUT`.
 - viii. For example, in case of the value of the general constraint flag `intra_only_constraint_flag` is equal to 1, the signalling of the one or more of inter-related SPS syntax elements (such as `sps_weighted_pred_flag`, `sps_weighted_bipred_flag`, `long_term_ref_pics_flag`, `sps_idr_rpl_present_flag`, `rpl1_same_as_rpl0_flag`, `gdr_enabled_flag`, `res_change_in_clvs_allowed_flag`, `sps_ref_wraparound_enabled_flag`, `sps_temporal_mvp_enabled_flag`, `sps_sbtmvp_enabled_flag`, `sps_amvr_enabled_flag`, `sps_bdof_enabled_flag`, `sps_dmvr_enabled_flag`, `sps_sbt_enabled_flag`, `sps_affine_enabled_flag`, `sps_bcw_enabled_flag`, `sps_ciip_enabled_flag`, `sps_fpel_mmvd_enabled_flag`, `sps_gpm_enabled_flag`, and etc.) may be skipped.
 - ix. Additionally, when `intra_only_constraint_flag` is equal to 1, the value of each of the above-mentioned the inter-related SPS syntax elements is inferred to be equal to 0.
 - x. For example, the signalling of the corresponding SPS syntax element Y1 may be skipped in case of the value of the general constraint flag Y2 is equal to 1.
 - a) Additionally, when not present (in the case of the general constraint flag Y2 is equal to 1), the value of the corresponding SPS syntax element Y1 is inferred to be equal to 0.
 - b) For example, Y1 is `sps_ladf_enabled_flag`, and Y2 is `no_ladf_constraint_flag`.
 - c) For example, Y1 is `gdr_enabled_flag`, and Y2 is `no_gdr_constraint_flag`.
 - d) For example, Y1 is `res_change_in_clvs_allowed_flag`, and Y2 is `no_res_change_in_clvs_constraint_flag`.
 - e) For example, Y1 is `qtbtt_dual_tree_intra_flag`, and Y2 is `no_qtbtt_dual_tree_intra_constraint_flag`.
 - f) For example, Y1 is `partition_constraints_override_enabled_flag`, and Y2 is `no_partition_constraints_override_constraint_flag`.
 - g) For example, Y1 is `sps_joint_cbr_enabled_flag`, and Y2 is `no_joint_cbr_constraint_flag`.
 - h) For example, Y1 is `sps_sao_enabled_flag`, and Y2 is `no_sao_constraint_flag`.
 - i) For example, Y1 is

sps_alf_enabled_flag, and Y2 is no_alf_constraint_flag. j) For example, Y1=sps_ccalf_enabled_flag, Y2=no_ccalf_constraint_flag. k) For example, Y1 is sps_transform_skip_enabled_flag, and Y2 is no_transform_skip_constraint_flag. l) For example, Y1 is sps_bdpcm_enabled_flag, and Y2 is no_bdpcm_constraint_flag. m) For example, Y1 is sps_ref_wraparound_enabled_flag, and Y2 is no_ref_wraparound_constraint_flag. n) For example, Y1=sps_temporal_mvp_enabled_flag, Y2=no_temporal_mvp_constraint_flag. o) For example, Y1 is sps_sbtmvp_enabled_flag, and Y2 is no_sbtmvp_constraint_flag. p) For example, Y1 is sps_amvr_enabled_flag, and Y2 is no_amvr_constraint_flag. q) For example, Y1 is sps_bdof_enabled_flag, and Y2 is no_bdof_constraint_flag. r) For example, Y1 is sps_dmvr_enabled_flag, and Y2 is no_dmvr_constraint_flag. s) For example, Y1 is sps_cclm_enabled_flag, and Y2 is no_cclm_constraint_flag. t) For example, Y1 is sps_mts_enabled_flag, and Y2 is no_mts_constraint_flag. u) For example, Y1 is sps_sbt_enabled_flag, and Y2 is no_sbt_constraint_flag. v) For example, Y1 is sps_affine_enabled_flag, and Y2 is no_affine_motion_constraint_flag. w) For example, Y1 is sps_bcw_enabled_flag, and Y2 is no_bcw_constraint_flag. x) For example, Y1 is sps_ibc_enabled_flag, and Y2 is no_ibc_constraint_flag. y) For example, Y1 is sps_ciip_enabled_flag, and Y2 is no_ciip_constraint_flag. z) For example, Y1 is sps_fpel_mmvd_enabled_flag, and Y2 is no_fpel_mmvd_constraint_flag. aa) For example, Y1 is sps_dep_quant_enabled_flag, and Y2 is no_dep_quant_constraint_flag. bb) For example, Y1 is sps_sign_data_hiding_enabled_flag, and Y2 is no_sign_data_hiding_constraint_flag. cc) For example, Y1 is sps_gpm_enabled_flag, and Y2 is no_gpm_constraint_flag.

vi. Alternatively, a bitstream constraint may be added to require that the value of the related syntax element in SPS be equal to a certain value based on the value of the corresponding general constraint flag. a) In one example (in this case the above mentioned SPS syntax element Y1 is signalled or inferred), a bitstream constraint may be added that when the general constraint flag Y2 is equal to 1, the value of the corresponding SPS syntax element Y1 is required to be equal to 0. b) In one example (in this case the APS-related SPS syntax element is signalled or inferred), a bitstream constraint may be added that when no_aps_constraint_flag is equal to 1, the value of each of the APS-related SPS syntax elements (such as sps_lmcs_enabled_flag, sps_scaling_list_enabled_flag, sps_alf_enabled_flag, sps_ccalf_enabled_flag, and etc.) is required to be equal to 0. c) In one example (in this case the inter-related SPS syntax element is signalled or inferred), a bitstream constraint may be added that when intra_only_constraint_flag is equal to 1, the value of each of the above inter-related SPS syntax elements (such as sps_weighted_pred_flag, sps_weighted_bipred_flag, long_term_ref_pics_flag, sps_idr_rpl_present_flag, rpl1_same_as_rpl0_flag, gdr_enabled_flag, res_change_in_clvs_allowed_flag, sps_ref_wraparound_enabled_flag, sps_temporal_mvp_enabled_flag, sps_sbtmvp_enabled_flag, sps_amvr_enabled_flag, sps_bdof_enabled_flag, sps_dmvr_enabled_flag, sps_sbt_enabled_flag, sps_affine_enabled_flag, sps_bcw_enabled_flag, sps_ciip_enabled_flag, sps_fpel_mmvd_enabled_flag, sps_gpm_enabled_flag, and etc.) is required to be equal to 0.

b. In one example, signalling of one or multiple PH syntax elements may be skipped according to the values of some general constraint flags. i. For example, when intra_only_constraint_flag is equal to 1, the signalling of the inter-related PH syntax elements such as ph_inter_slice_allowed_flag may be skipped. a) Additionally, when intra_only_constraint_flag is equal to 1, the value of each of the inter-related PH syntax elements such as ph_inter_slice_allowed_flag is inferred to be equal to 0. ii. For example, when intra_only_constraint flag is equal to 1, the signalling of the PH syntax elements in the syntax structure ref_pic_lists() and the syntax structure ref_pic_list_struct(listIdx, rplsIdx) included in the PH may be skipped. a) For example, when intra_only_constraint_flag is equal to 1, the syntax elements such as rpl_sps_flag[], rpl_idx[], poc_lsb_lt[], delta_poc_msb_present_flag[], delta_poc_msb_cycle_lt[][] in the syntax structure ref_pic_lists() that included in the PH may be skipped. b) For example, when intra_only_constraint_flag is equal to 1, the syntax elements such as num_ref_entries[], ltrp_in_header_flag[][], inter_layer_ref_pic_flag[][][], st_ref_pic_flag[], abs_delta_poc_st[], strp_entry_sign_flag[][][], rpls_poc_lsb_lt[], ilrp_idx[][][] in the syntax structure ref_pic_list_struct(listIdx, rplsIdx) that included in the PH may be skipped. iii. Alternatively (in this case the corresponding syntax elements in PH are not conditionally signalled or skipped depending on the values of related general constraint flags/fields), in one example, a bitstream constraint may be added to require that the value of the related syntax element in PH be equal to a certain value based on the value of the

corresponding general constraint flag. a) In one example (in this case the PH syntax element `ph_inter_slice_allowed_flag` is signalled or inferred), when `intra_only_constraint_flag` is equal to 1, a bitstream constraint may be added such that the value of each of the inter-related PH syntax elements such as `ph_inter_slice_allowed_flag` is required to be equal to 0. b) In one example (in this case the syntax elements in `ref_pic_lists()` and `ref_pic_list_struct(listIdx, rplsIdx)` included in the PH are signalled or inferred), a bitstream constraint may be added that the syntax elements in reference picture lists included in PH are required to be never used. c. In one example, signalling of one or multiple SH syntax elements may be skipped according to the values of some general constraint flags. i. For example, the signalling of the RPL-related SH syntax element `num_ref_idx_active_override_flag` may be skipped, in case of the value of `intra_only_constraint_flag` is equal to 1. a) Additionally, when `intra_only_constraint_flag` is equal to 1, the value of `num_ref_idx_active_override_flag` is inferred to be equal to 0. ii. For example, in case of `intra_only_constraint_flag` is equal to 1, the signalling of the RPL-related syntax elements in the syntax structure `ref_pic_lists()` and the syntax structure `ref_pic_list_struct(listIdx, rplsIdx)` included in the SH may be skipped. a) For example, when `intra_only_constraint_flag` is equal to 1, the syntax elements such as `rpl_sps_flag[]`, `rpl_idx[]`, `poc_lsb_lt[][]`, `delta_poc_msb_present_flag[][]`, `delta_poc_msb_cycle_lt[][]` in the syntax structure `ref_pic_lists()` that included in the SH may be skipped. b) For example, when `intra_only_constraint_flag` is equal to 1, the syntax elements such as `num_ref_entries[][]`, `ltrp_in_header_flag[][]`, `inter_layer_ref_pic_flag[][]`, `st_ref_pic_flag[][]`, `abs_delta_poc_st[][]`, `strp_entry_sign_flag[][]`, `rpls_poc_lsb_lt[][]`, `ilrp_idx[][]` in the syntax structure `ref_pic_list_struct(listIdx, rplsIdx)` that included in the SH may be skipped. iii. Alternatively (in this case the corresponding syntax elements in SH are not conditionally signalled or skipped depending on the values of related general constraint flags/fields), in one example, a bitstream constraint may be added to require that the value of each of the related syntax elements in SH is be equal to a certain value according to the value of the corresponding general constraint flag. a) In one example (in this case the SH syntax element `num_ref_idx_active_override_flag` is signalled or inferred), when `intra_only_constraint_flag` is equal to 1, a bitstream constraint may be added such that the syntax element `num_ref_idx_active_override_flag` in SH is required to be equal to 0. b) In one example (in this case the SH syntax elements in `ref_pic_lists()` and `ref_pic_list_struct(listIdx, rplsIdx)` included in the SH are signalled or inferred), when `intra_only_constraint_flag` is equal to 1, a bitstream constraint may be added such that the syntax elements in reference picture lists included in SH are required to be never used. d. In above examples, the general constraint flags/fields used to determine whether signalling of one or multiple SH syntax elements is skipped may be replaced by a new syntax element in SPS/PPS/PH/SH. e. In above examples, the general constraint flags/fields used to determine whether signalling of one or multiple PH syntax elements is skipped may be replaced by a new syntax element in SPS/PPS/PH. f. In above examples, the general constraint flags/fields used to determine whether signalling of one or multiple SPS syntax elements is skipped may be replaced by a new syntax element in SPS. 3. Regarding the constraints of PPS syntax elements based on the general constraint flags for solving the third problem: 1) Depending on the values of general constraint flags, the values of the corresponding syntax elements in PPS may be constrained, e.g., as in the second embodiment. a. In one example, depending on the values of general constraint flags, bitstream constraints may be added such that the value of a syntax element in PPS is required to be equal to a certain value. i. For example, when `one_tile_per_pic_constraint_flag` is equal to 1, the values of `num_exp_tile_columns_minus1`, and/or `num_exp_tile_rows_minus1`, and/or `rect_slice_flag` are required to be equal to 0. ii. For example, when `one_slice_per_pic_constraint_flag` is equal to 1, the value of `rect_slice_flag` is required to be equal to 1. iii. For example, when both `one_tile_per_pic_constraint_flag` and `one_slice_per_pic_constraint_flag` are equal to 1, the value of `no_pic_partition_flag` is required to be equal to 1. iv. For example, when `intra_only_constraint_flag` is equal to 1, the values of `rpl1_idx_present_flag` and `num_ref_idx_default_active_minus1[]` are required to be equal to 0. 4. Regarding the constraints on general constraint flags to disallow illegal values of such general constraint flags for solving the fourth problem: 1) In the syntax `general_constraint_info()` the value of one general constraint flag may be dependent on the value of another general constraint flag, e.g., as in the third embodiment. a. In one example, depending on the values of earlier signalled general constraint flags, the signalling of some general constraint flags in the syntax `general_constraint_info()` may be skipped. i. In one example, in case of the value of `one_slice_per_pic_constraint_flag` is equal to 1,

the signalling of the syntax element `one_subpic_per_pic_constraint_flag` in the syntax `general_constraint_info()` may be skipped. 1. Additionally, when `one_slice_per_pic_constraint_flag` is equal to 1, the value of `one_subpic_per_pic_constraint_flag` is inferred to be equal to 1. ii. In one example, in case of the value of `no_transform_skip_constraint_flag` is equal to 1, the signalling of the syntax element `no_bdpcm_constraint_flag` in the syntax `general_constraint_info()` may be skipped. 1. Additionally, when `no_transform_skip_constraint_flag` is equal to 1, the value of `no_bdpcm_constraint_flag` is inferred to be equal to 1. iii. For example, in case of the value of `intra_only_constraint_flag` is equal to 1, the signalling of the inter-related syntax elements (such as `no_res_change_in_clvs_constraint_flag`, `no_ref_wraparound_constraint_flag`, `no_temporal_mvp_constraint_flag`, `no_sbtmvp_constraint_flag`, `no_amvr_constraint_flag`, `no_bdof_constraint_flag`, `no_dmvr_constraint_flag`, `no_sbt_constraint_flag`, `no_affine_motion_constraint_flag`, `no_bcw_constraint_flag`, `no_ciip_constraint_flag`, `no_fpel_mmvd_constraint_flag`, `no_gpm_constraint_flag`) in the `general_constraint_info()` syntax structure may be skipped. 2. Additionally, when `intra_only_constraint_flag` is equal to 1, the value of each of the above-mentioned inter-related syntax elements in the `general_constraint_info()` syntax structure is inferred to be equal to 1. b. In one example, alternatively (in this case the general constraint flags are not conditionally signalled or skipped depending on values of earlier general constraint flags), bitstream constraints may be added such that the value of one general constraint flag is required to be equal to a certain value according to the value of the related earlier general constraint flag(s). i. In one example, when `intra_only_constraint_flag` is equal to 1, the value of each of the inter-related general constraint flags as mentioned in the above bullet is required to be equal to 1. ii. In one example, when `intra_only_constraint_flag` is equal to 1, at least one of the values of `no_idr_constraint_flag` and `no_cra_constraint_flag` is required to be equal to 0. iii. In one example, when `no_transform_skip_constraint_flag` equal to 1, the value of `no_bdpcm_constraint_flag` is required to be equal to 1. iv. In one example, when `no_aps_constraint_flag` is equal to 1, the value of `no_alf_constraint_flag` is required to be equal to 1. c. In one example, additionally, bitstream constraints may be added to require the values of some general constraint flags be equal to certain values, and, if necessary, under certain conditions. i. In one example, a bitstream constraint may be added to constrain the values of the combination of multiple general constraint flags, e.g., at least one of the values of `no_gdr_constraint_flag`, `no_idr_constraint_flag`, and `no_cra_constraint_flag` is required to be equal to 0. ii. In one example, a bitstream constraint may be added to constrain the range of general constraint fields. 1. For example, `max_bitdepth_constraint_idc` is required to be in the range of 0 to X (such as X=8), inclusive. 2. For example, when `general_profile_idc` is equal to A (such as A=1), `max_bitdepth_constraint_idc` is required to be in the range of 0 to B (such as B=2), inclusive. 5. Regarding adding new SPS/PPS syntax elements for solving the fifth problem: 1) New SPS and/or PPS syntax elements may be added to condition the related syntax elements in SPS/PPS/PH/SH, e.g., as in the fourth embodiment. a. In one example, a new SPS syntax element (e.g., `sps_intra_only_flag`) and/or a new PPS syntax element (e.g., `pps_intra_only_flag`) may be added to condition the inter prediction related syntax elements in SPS/PPS/PH/SH. i. In one example, when the general constraint flag `intra_only_constraint_flag` is equal to 1, the signalling of the new SPS syntax element `sps_intra_only_flag` and/or the new PPS syntax element `pps_intra_only_flag` may be skipped. 1. Additionally, when `intra_only_constraint_flag` is equal to 1, the value of the new SPS syntax element `sps_intra_only_flag` is inferred to be equal to 1, and/or, the value of the new PPS syntax element `pps_intra_only_flag` is inferred to be equal to 1. ii. In one example, in case of the value of the new SPS syntax element (e.g., `sps_intra_only_flag`) is equal to 1, the signalling of the inter-related SPS syntax elements (such as `sps_weighted_pred_flag`, `sps_weighted_bipred_flag`, `long_term_ref_pics_flag`, `sps_idr_rpl_present_flag`, `rpl1_same_as_rpl0_flag`, `gdr_enabled_flag`, `res_change_in_clvs_allowed_flag`, `sps_ref_wraparound_enabled_flag`, `sps_temporal_mvp_enabled_flag`, `sps_sbtmvp_enabled_flag`, `sps_amvr_enabled_flag`, `sps_bdof_enabled_flag`, `sps_dmvr_enabled_flag`, `sps_sbt_enabled_flag`, `sps_affine_enabled_flag`, `sps_bcw_enabled_flag`, `sps_ciip_enabled_flag`, `sps_fpel_mmvd_enabled_flag`, `sps_gpm_enabled_flag`, and etc.) may be skipped. 2. Additionally, when the new SPS syntax element `sps_intra_only_flag` is equal to 1, the value of each of the inter-related SPS syntax elements is inferred to be equal to a certain value (such as 0 or 1). iii. In one example, in case of the value of the new SPS/PPS

syntax element (e.g., `sps_intra_only_flag`, and/or `pps_intra_only_flag`) is equal to 1, the signalling of the corresponding inter-related and RPL-related syntax elements included in PH and/or SH may be skipped.

1. In one example, the above-mentioned inter-related PH syntax element may be `ph_inter_slice_allowed_flag`. 2. In one example, the above-mentioned RPL-related SH syntax element may be `num_ref_idx_active_override_flag`. 3. In one example, the above-mentioned corresponding RPL-related syntax element may be the syntax elements in the syntax structure `ref_pic_lists()` and the syntax structure `ref_pic_list_struct(listIdx, rplIdx)` included in the PH and/or SH. 4. Additionally, when the new syntax element `sps_intra_only_flag`, and/or `pps_intra_only_flag` is equal to 1, the value of each of the corresponding inter-related and RPL-related syntax elements in PH and/or SH is inferred to be equal a certain value (such as 0 or 1). iv. In one example, in case of the value of the new PPS syntax element (e.g., `pps_intra_only_flag`) is equal to 1, the signalling of the corresponding PPS syntax elements may be skipped. 1. For example, the above-mentioned corresponding PPS syntax element may be `rpl1_idx_present_flag`. 2. For example, the above-mentioned corresponding PPS syntax element may be `num_ref_idx_default_active_minus1[]`. 3. Additionally, when the new PPS syntax element `pps_intra_only_flag` is equal to 1, the value of the corresponding PPS syntax elements is inferred to be equal to a certain value (such as 0 or 1). v. Alternatively (in this case the new SPS and/or PPS syntax elements `sps_intra_only_flag` and/or `pps_intra_only_flag` is conditionally signalled or skipped depending on the values of `intra_only_constraint_flag`), in one example, when `intra_only_constraint_flag` is equal to 1, bitstream constraints may be added to require the value of the new SPS and/or PPS syntax elements `sps_intra_only_flag` and/or `pps_intra_only_flag` to be equal to 1. vi. Alternatively (in this case the SPS/PPS/PH/SH syntax elements related to the new SPS/PPS syntax elements are not conditionally signalled or skipped depending on the values of the new SPS/PPS syntax elements), in one example, according to the values of the new SPS/PPS syntax elements, bitstream constraints may be added that the value of each of the related syntax elements in SPS/PPS/PH/SH is required to be equal to a certain value (such as 0 or 1). 1. In one example (in this case the new PPS syntax element `pps_intra_only_flag` is signalled or inferred), additionally, when the new SPS syntax element `sps_intra_only_flag` is equal to 1, a bitstream constraint may be added such that the value of the new PPS syntax element `pps_intra_only_flag` is required to be equal to 1. 2. In one example (in this case the SPS syntax elements related to the new SPS syntax elements are signalled or inferred), a bitstream constraint may be added such that when the new SPS syntax element `sps_intra_only_flag` is equal to 1, the value of the inter-related SPS syntax element is required to be equal to 0. 3. In one example (in this case the PPS syntax elements related to the new SPS/PPS syntax elements are signalled or inferred), in one example, a bitstream constraint may be added such that when the new SPS syntax element `sps_intra_only_flag` is equal to 1, or, the new PPS syntax element `pps_intra_only_flag` is equal to 1, the value of inter-related PPS syntax elements is required to be equal to 0. 4. In one example (in this case the PH/SH syntax elements related to the new SPS/PPS syntax elements are signalled or inferred), a bitstream constraint may be added such that when the new SPS syntax element `sps_intra_only_flag` is equal to 1 and/or the new PPS syntax element `pps_intra_only_flag` is equal to 1, the value of the corresponding inter-related and/or RPL-related syntax element included in PH/SH is required to be equal to a certain value (such as 0 or 1). 6. Regarding adding new general constraint flags/fields for solving the sixth problem: 1) In the syntax `general_constraint_info()` new general constraint flags may be added, and furthermore, these new general constraint flags may be used to condition the related syntax elements in SPS/PPS/PH/SH, or to constrain the values of related syntax elements in SPS/PPS/PH/SH through bitstream constraints, e.g., as in the fifth embodiment. a. For example, a new general constraint flag may be added to achieve one or more functionalities as described below. i. For example, add a new general constraint flag to disable the inter-layer prediction and/or allowing only one layer, e.g., a new syntax element `no_inter_layer_prediction_constraint_flag` is added. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `inter_layer_ref_pics_present_flag` or to constrain its value. ii. For example, add a new general constraint flag to disable long-term reference, e.g., a new syntax element `no_long_term_ref_pics_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `long_term_ref_pics_flag` or to constrain its value. iii. For example, add a new general constraint flag to disable max transform size equal to 32×32, e.g., a new syntax element `no_max_luma_transform_size_64_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the

SPS syntax element `sps_max_luma_transform_size_64_flag` or to constrain its value. iv. For example, add a new general constraint flag to disable MER, e.g., a new syntax element `no_parallel_merge_level_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `log2_parallel_merge_level_minus2` or to constrain its value. v. For example, add a new general constraint flag to disable the presence of the wavefront parallel processing entry offsets, e.g., a new syntax element `no_wpp_entry_point_offset_present_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_wpp_entry_point_offsets_present_flag` or to constrain its value. vi. For example, add a new general constraint flag to disable the entropy coding sync point (i.e., wavefront parallel processing), e.g., a new syntax element `no_entropy_coding_sync_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_entropy_coding_sync_enabled_flag` or to constrain its value. b. For example, a new general constraint flag may be added to control one or more of the coding tools as described below. i. For example, add a new general constraint flag to disable weighted prediction for P slices, e.g., a new syntax element `no_weighted_pred_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_weighted_pred_flag` or to constrain its value. ii. For example, add a new general constraint flag to disable the weighted bi-prediction for B slices, e.g., a new syntax element `no_weighted_bipred_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_weighted_bipred_flag` or to constrain its value. iii. For example, add a new general constraint flag to disable the SMVD, e.g., a new syntax element `no_smvd_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_smvd_enabled_flag` or to constrain its value. iv. For example, add a new general constraint flag to disable the MMVD, e.g., a new syntax element `no_mmvd_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_mmvd_enabled_flag` or to constrain its value. v. For example, add a new general constraint flag to disable the ISP, e.g., a new syntax element `no_isp_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_isp_enabled_flag` or to constrain its value. vi. For example, add a new general constraint flag to disable the MRL, e.g., a new syntax element `no_mrl_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_mrl_enabled_flag` or to constrain its value. vii. For example, add a new general constraint flag to disable the MIP, e.g., a new syntax element `no_mip_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_mip_enabled_flag` or to constrain its value. viii. For example, add a new general constraint flag to disable the PLT, e.g., a new syntax element `no_palette_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_palette_enabled_flag` or to constrain its value. ix. For example, add a new general constraint flag to disable the ACT, e.g., a new syntax element `no_act_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_act_enabled_flag` or to constrain its value. x. For example, add a new general constraint flag to disable the LMCS, e.g., a new syntax element `no_lmcs_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_lmcs_enabled_flag` or to constrain its value. xi. For example, add a new general constraint flag to disable the LFNST, e.g., a new syntax element `no_lfnst_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_lfnst_enabled_flag` or to constrain its value. xii. For example, add a new general constraint flag to disable the scaling list, e.g., a new syntax element `no_scaling_list_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_scaling_list_enabled_flag` or to constrain its value. xiii. For example, add a new general constraint flag to disable the virtual boundaries, e.g., a new syntax element `no_virtual_boundaries_constraint_flag`. Furthermore, this new syntax element may be used to condition the signalling of the SPS syntax element `sps_virtual_boundaries_enabled_flag` or to constrain its value. c. For example, a new general constraint flag may be added to control (i.e., to condition the signalling of or to constrain the values of) a group of syntax elements as described below. i. For example, add a new general constraint flag to disable the weighted prediction and weighted bi-prediction. Furthermore, this new syntax element may be used to

control the SPS syntax elements `sps_weighted_pred_flag` and `sps_weighted_bipred_flag`. d. For example, when the new general constraint syntax is equal to 1, the signalling of the corresponding SPS/PH/SH syntax element may be skipped. ii. Additionally, when the corresponding SPS/PH/SH syntax element is not present (in the case of the corresponding new general constraint syntax element is equal to 1), the value of the corresponding SPS/PH/SH syntax element is inferred to be equal to a certain value (such as 0 or 1). iii. Alternatively (in this case of the corresponding SPS/PH/SH syntax element is signalled or inferred), in one example, a bitstream constraint may be added such that when the new general constraint syntax element is equal to 1, the value of the corresponding SPS/PH/SH syntax element is required to be equal to a certain value (such as 0 or 1). i. Alternatively, in one example, when `no_aps_constraint_flag` is equal to 1, the values of the APS-related newly added constraint flags (e.g., `no_scaling_list_constraint_flag` and `no_lmcs_constraint_flag`) are required to be equal to 1. ii. Alternatively, in one example, when `intra_only_constraint_flag` is equal to 1, the values of the APS-related newly added constraint flags (e.g., `no_weighted_pred_constraint_flag`, `no_weighted_bipred_constraint_flag`, `no_long_term_ref_pics_constraint_flag`, `no_inter_layer_prediction_constraint_flag`, `no_smvd_constraint_flag`, and `no_mmvd_constraint_flag`) are required to be equal to 1. iii. Alternatively, in one example, when `vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]]` is equal to 1, the value of `no_inter_layer_prediction_constraint_flag` is required to be equal to 1.

7. Regarding the connection of APS syntax elements to the syntax elements in the other parameter sets for solving the seventh problem: 1) In one example, VPS ID and/or SPS ID and/or PPS ID may be added to APS syntax structure, i.e., `adaptation_parameter_set_rbsp( )`, e.g., as in the sixth embodiment. 2) In one example, the APS syntax elements (e.g., `alf_luma_filter_signal_flag`, `alf_chroma_filter_signal_flag`, `alf_cc_cb_filter_signal_flag` and `alf_cc_cr_filter_signal_flag`) may be dependent on the value of general constraint flag, e.g., as in the sixth embodiment. a. For example, when `no_aps_constraint_flag` is equal to 0, at least one of the values of `alf_luma_filter_signal_flag`, `alf_chroma_filter_signal_flag`, `alf_cc_cb_filter_signal_flag` and `alf_cc_cr_filter_signal_flag` shall be equal to 1. b. For example, when `sps_alf_enabled_flag` is equal to 1, at least one of the values of `alf_luma_filter_signal_flag`, `alf_chroma_filter_signal_flag`, `alf_cc_cb_filter_signal_flag` and `alf_cc_cr_filter_signal_flag` shall be equal to 1. c. When `no_aps_constraint_flag` is equal to 0 and `sps_alf_enabled_flag` is equal to 1, at least one of the values of `alf_luma_filter_signal_flag`, `alf_chroma_filter_signal_flag`, `alf_cc_cb_filter_signal_flag` and `alf_cc_cr_filter_signal_flag` shall be equal to 1. d. Alternatively, the values of `alf_luma_filter_signal_flag`, `alf_chroma_filter_signal_flag`, `alf_cc_cb_filter_signal_flag` and `alf_cc_cr_filter_signal_flag` may be dependent on whether there is a APS NAL unit having `aps_params_type` equal to `ALF_APS`. 3) In one example, the APS syntax elements may be dependent on the value of a syntax element associated with the corresponding SPS/PPS according to the SPS/PPS ID. a. For example, the value of chroma-related APS syntax elements (such as `alf_chroma_filter_signal_flag`, `alf_cc_cb_filter_signal_flag`, `alf_cc_cr_filter_signal_flag`, `scaling_list_chroma_present_flag`, and etc.) may not be constrained according to variables (such as `ChromaArrayType`) derived by the SPS syntax elements. 4) In one example, bitstream constraints may be added that when `no_aps_constraint_flag` is equal to 1, the syntax elements associated with the syntax structures `alf_data( )`, `lmcs_data( )` and `scaling_list_data( )` cannot be sent.

8. Regarding redundant signalling of the general constraint flags: 1) In one example, indicators may be included in the syntax structures of `profile_tier_level( )` and/or `general_constraint_info( )` to indicate which profile and/or which tier and/or which level that the current general constraint information applies to. 2) In one example, the syntax structure `general_constraint_info( )` may be and may only be included in the SPS syntax structure `seq_parameter_set_rbsp( )`. 3) Bitstream constraint may be added that if there is VPS, the `general_constraint_info( )` syntax elements included in VPS are used for the CVS. 4) Bitstream constraint may be added that if there is NO VPS, the `general_constraint_info( )` syntax elements included in SPS are used for the current CLVS. 9. In one example, whether and/or how to signal the general constraint structure may depend on the values of the profile and/or the sub-profiles and/or level and/or tier. a. In one example, each `general_constraint_info( )` syntax structure is specified to be associated with one set of `general_profile_idc` and `subprofile_sub_profile_idc[i]` for all *i* values signalled in the same `profile_tier_level( )` syntax structure as the `general_constraint_info( )` syntax structure. Or equivalently, each `general_constraint_info( )` syntax structure is specified to be associated with the `profile_tier_level( )`

syntax structure containing the `general_constraint_info()` syntax structure. b. In one example, the information carried in a `general_constraint_info()` syntax structure may impose more constraints regarding which coding tools can be applied than the profile and sub-profiles indicated in the `profile_tier_level()` syntax structure containing the `general_constraint_info()` syntax structure. That means, in addition to all the constraints imposed by the profile and sub-profiles, more aspects may be constrained by the general constraint information. c. In one example, for any particular aspect associated with a general constraint syntax element, the corresponding general constraint syntax element has to have a value that indicates either a tighter constraint regarding that aspect than indicated by the profile and sub-profiles or the same constraint regarding that aspect as indicated by the profile and sub-profiles. i. In one example, if any of the profile and sub-profiles indicates that all slices are intra slices, then the `intra_only_constraint_flag` shall be equal to 1, whereas if none of the profile and sub-profiles indicates that all slices are intra slices, the `intra_only_constraint_flag` may be equal to either 1 or 0. d. In one example, for any particular aspect associated with a general constraint syntax element, the tightest constraint indicated by the profile, the sub-profiles, and the corresponding general constraint syntax element applies. i. In one example, when any of the profile and sub-profiles indicates that all slices are intra slices, the value of `intra_only_constraint_flag` may be equal to either 1 or 0, but still all slices are required to be intra slices, and when none of the profile and sub-profiles indicates that all slices are intra slices and the value of `intra_only_constraint_flag` is equal to 1, again all slices are required to be intra slices. e. In one example, no general constraint information is signalled for a specific profile and/or sub-profile and/or level and/or tier. The general constraint flags/fields are inferred to be predefined values based on the specific profile and/or level and/or tier. f. In one example, the general constraint information may be signalled but ignored for a specific profile and/or sub-profile and/or level and/or tier. The general constraint flags are inferred to be predefined values based on the specific profile and/or level and/or tier. g. In one example, the general constraint information may be signalled for a specific profile and/or sub-profile and/or level and/or tier. The general constraint flags must be equal to predefined values based on the specific profile and/or level and/or tier in a conformance bitstream. h. In one example, the general constraint information may be signalled for a specific profile and/or sub-profile and/or level and/or tier. Whether and/or how to apply a coding tool may be determined by the corresponding general constraint flag(s), ignoring the specification in the profile and/or level and/or tier. i. In one example, the general constraint flag associated with a coding tool must be set equal to 1 (meaning turned off) if the coding tool is specified to be turned off in the profile and/or sub-profile and/or level and/or tier. j. In one example, the general constraint flag associated with a coding tool may be ignored and inferred to be 1 (meaning turned off) if the coding tool is specified to be turned off in the profile and/or sub-profile and/or level and/or tier. k. In one example, the general constraint flag associated with a coding tool may be skipped and inferred to be 1 (meaning turned off) if the coding tool is specified to be turned off in the profile and/or sub-profile and/or level and/or tier. l. In one example, for a profile and/or sub-profile a sub-profile indicating all intra coding, `intra_only_constraint_flag` must be equal to 1. i. Alternatively, for a profile and/or sub-profile a sub-profile indicating all intra coding, `intra_only_constraint_flag` is skipped or ignored and inferred to be 1. 10. Regarding the presence and the value of the syntax element (e.g., `X_info_in_ph_flag` in the PPS), for solving the eighth problem: a. It is proposed that the presence of the syntax element (e.g., `X_info_in_ph_flag` in the PPS), specifying whether the associated information of a certain feature is signalled in the PH or SH, is conditioned on whether there is partition/split of the pictures referring to the PPS (e.g., whether `no_pic_partition_flag` is equal to 1). i. Alternatively, the presence of `X_info_in_ph_flag` in the PPS may be conditioned on whether there is only one slice in the pictures referring to the PPS. ii. Additionally, infer `X_info_in_ph_flag` to be equal to a certain value (such as 0 or 1) when not present. 1. Alternatively, if the feature X is dependent on the APS syntax elements, then infer `X_info_in_ph_flag` to be equal to 1 when not present. 2. Alternatively, if the feature X is not dependent on the APS syntax elements, then infer `X_info_in_ph_flag` to be equal to 0 when not present. b. Additionally, the value of `X_info_in_ph_flag` may be constrained based on whether PH syntax structure is present in the slice header. i. For example, it is required that, when `picture_header_in_slice_header_flag` is equal to 1, the value of `X_info_in_ph_flag` is required to be equal to a certain value (such as 0 or 1). c. For example, X may be chroma QP offsets (suppose a flag named `chroma_qp_offset_info_in_ph_flag` is signalled in the PPS to control whether to signal chroma QP offsets in the PH or SH). d. For example, X may be any

feature or information associated with the PH or SH. 11. Regarding removing the semantics dependency of APS on SPS, for solving the ninth problem: a. In one example, a syntax element (e.g., named `aps_chroma_present_flag`) may be signalled in the APS syntax structure (e.g., `adaptation_parameter_set_rbsp( )` specifying whether the chroma-related APS syntax elements would be signalled or not b. For example, `ChromaArrayType` derived by SPS syntax elements is achievable through the SPS/PPS ID associated with the PH/SH syntax elements. c. In one example, the constraints of APS syntax elements (e.g., `aps_chroma_present_flag`) may be dependent on variables (e.g., `ChromaArrayType`) derived from the PH or SH syntax elements. d. In one example, the constraints and signalling are applied as in the seventh embodiment. e. In one example, the constraints and signalling are applied as in the eighth embodiment. f. For example, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_luma[i]` shall be equal to 1 when `ChromaArrayType` is not equal to 0. i. Alternatively, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_chroma` shall be equal to 1 when `ChromaArrayType` is not equal to 0. ii. Alternatively, additionally, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_cc_alf_cb_aps_id` shall be equal to 1 when `ChromaArrayType` is not equal to 0. iii. Alternatively, additionally, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_cc_alf_cr_aps_id` shall be equal to 1 when `ChromaArrayType` is not equal to 0. g. Additionally, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_luma[1]` shall be equal to 0 when `ChromaArrayType` is equal to 0. h. Additionally, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `slice_alf_aps_id_luma[i]` shall be equal to 1 when `ChromaArrayType` is not equal to 0. i. Alternatively, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `slice_alf_aps_id_chroma` shall be equal to 1 when `ChromaArrayType` is not equal to 0. ii. Alternatively, additionally, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `slice_cc_alf_cb_aps_id` shall be equal to 1 when `ChromaArrayType` is not equal to 0. iii. Alternatively, additionally, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `slice_cc_alf_cr_aps_id` shall be equal to 1 when `ChromaArrayType` is not equal to 0. i. Additionally, it is required that, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `slice_alf_aps_id_luma[i]` shall be equal to 0 when `ChromaArrayType` is equal to 0. 12. It is proposed that a SE (e.g. named as “`general_pic_header_in_slice_header_constraint_flag`”) is signalled in the general constrained syntax structure (such as `general_constraint_info( )` in VVC) to indicate whether picture header information shall be signalled in the slice header. a. For example, it is required that picture header information shall be signalled in the slice header when `general_pic_header_in_slice_header_constraint_flag` is equal to 0. b. For example, it is required that picture header information shall be signalled in the slice header when `general_pic_header_in_slice_header_constraint_flag` is equal to 1. c. It is required that the SE (such as `one_slice_per_pic_constraint_flag`), which indicates whether each picture shall contain only one slice, shall be equal to 1 when `general_pic_header_in_slice_header_constraint_flag` is equal to 0. d. It is required that the SE (such as `one_slice_per_pic_constraint_flag`), which indicates whether each picture shall contain only one slice, shall be equal to 1 when `general_pic_header_in_slice_header_constraint_flag` is equal to 1. 13. It is proposed that whether to allow partition a picture into rectangular slices or non-rectangular slices may be constrained by a bitstream conformance. a. Alternatively, whether to signal a picture header in a slice header may be constrained by a bitstream conformance depending on whether to partition a picture into rectangular slices or non-rectangular slices b. For example, a SE (such as `picture_header_in_slice_header_flag`) indicating whether to signal a picture header in a slice header shall be equal to 1 when partitioning a picture into rectangular slices (e.g. `rect_slice_flag` is equal to 1). c. For example, a SE (`rect_slice_flag`) indicating whether to partition a picture into rectangular slices shall be

equal to 1 when signalling a picture header (e.g. picture_header_in_slice_header_flag is equal to 1). 14. Regarding the GCI syntax structure signalling for solving the 10th problem, one or more of the following approaches are disclosed, e.g., as in the ninth embodiment: a. A new syntax element (e.g., a flag, named gci_present_flag) is signalled in the profile_tier_level() syntax structure to indicate the presence of the GCI SEs in the GCI syntax structure (e.g., general_constraint_info()) and/or the presence of the GCI syntax structure (e.g., general_constraint_info()) itself in the PTL syntax structure (e.g. profile_tier_level()). i. In one example, whether the GCI SEs in the GCI syntax structure are signalled or not are conditioned on the value of gci_present_flag. ii. In one example, if the syntax element specifies that the GCI is not present (e.g., gci_present_flag is equal to 0), then the GCI syntax structure (e.g., general_constraint_info()) is not signalled in the current profile_tier_level() syntax structure. iii. In one example, when the GCI syntax structure is not present in a profile_tier_level() syntax structure, or the GCI SEs in the GCI syntax structure are not present, it is specified that each of the GCI SEs is inferred to be the value such that the corresponding constraint is not imposed. For example, the value of the intra_only_constraint_flag is inferred to be equal to 0. 1. In one example, the following inference is specified: When gci_present_flag equal to 0 for a profile_tier_level() syntax structure with profileTierPresentFlag equal to 1 (and therefore the GCI syntax structure is not present in the profile_tier_level() syntax structure), the value of max_bitdepth_constraint_idc is inferred to be equal to 8, the value of max_chroma_format_constraint_idc is inferred to be equal to 3, and the value of the each of the other syntax elements in the general_constraint_info() syntax structure starting from general_non_packed_constraint_flag to no_aps_constraint_flag, inclusive, is inferred to be equal to 0. iv. In one example, when a GCI SE is not signalled, it may be inferred to be a default value, such as 0 or 1. 1. The default value may depend on profiles and/or levels. v. In one example, the signalling of gci_present_flag may be conditioned on profiles and/or levels. 1. When gci_present_flag is not signalled, it may be inferred to be a default value, such as 0 or 1. vi. In one example, gci_present_flag is u(1) coded. b. The starting position of the syntax element that specifies a level to which OlsInScope conforms (e.g., general_level_idc) is always a byte-aligned position. i. In one example, if the current position in the bitstream is not on a byte boundary, i.e., the next bit in the bitstream is not the first bit in a byte, then one or more syntax elements (e.g., ptl_alignment_zero_bit) are signalled right before general_level_idc until the starting position is byte aligned. 1. In one example, 0-valued syntax element (e.g., ptl_alignment_zero_bit) is coded with a fixed-pattern bit string using n bits written (from left to right) with the left bit first, wherein n=1, a.k.a., f(1) coded. c. The GCI syntax structure may not be byte aligned. i. In one example, general constraint flags are signalled in the GCI syntax structure, without checking if they are byte aligned or not. d. Reserved bits are signalled in the GCI syntax structure. i. In one example, the number of reserved bits is signalled in the GCI syntax structure, e.g., named gci_num_reserved_bits. ii. In one example, the number of reserved bits signalled in the GCI syntax structure is u(N) coded, such as N=11. iii. In one example, the number of reserved bits signalled in the GCI syntax structure is ue(v) coded. iv. In one example, reserved GCI syntax element (e.g., named gci_reserved_bit[i]) is signalled, wherein i ranges from 0 to gci_num_reserved_bits-1, inclusive. v. In one example, reserved GCI syntax element is u(X) coded, such as X=1. vi. In one example, the reserved bits must be byte-aligned. 1. In one example, the number of bytes of the reserved bits is signalled. 15. Regarding the semantics constraints of general constraint flags/fields for solving the 11.sup.th problem, one or more of the following approaches are disclosed, e.g., as in the ninth embodiment: a. In one example, when only slice_type equal to 1_SLICE is allowed (e.g., intra_only_constraint_flag is equal to 1), one or more constraints in the following may be specified: i. RPL-related SEs are constrained to a certain value that specifies the RPL is required to be not used. ii. Long term reference picture is required to be not allowed (e.g., the value of long_term_ref_pics_flag shall be equal to 0). iii. RPL is required to be not allowed for IDR pictures (e.g., the value of sps_idr_rpl_present_flag shall be equal to 0). iv. The number of reference picture lists is required to be equal to 0 (e.g., the value of sps_num_ref_pic_lists[i] shall be equal to 0). v. All layers shall be independent layers (e.g., the value of all_layers_independent_constraint_flag shall be equal to 1). vi. RPR is required to be not allowed (e.g., the value of no_ref_pic_resampling_constraint_flag shall be equal to 1). vii. Resolution change is required to be not allowed (e.g., the value of no_res_change_in_clvs_constraint_flag shall be equal to 1). viii. Weighted prediction for P slices is required to be not allowed. 1. A new syntax element (e.g., named no_weighted_pred_constraint_flag) may

be signalled in the GCI syntax structure to indicate whether weighted prediction for P slices shall be allowed or not. 2. In one example, when only slice_type equal to 1_SLICE is allowed (e.g., intra_only_constraint_flag is equal to 1), the value of no_weighted_bipred_constraint_flag shall be equal to 1. ix. Weighted prediction for B slices is required to be not allowed. 1. A new syntax element (e.g., named no_weighted_bipred_constraint_flag) may be signalled in the GCI syntax structure to indicate whether weighted prediction for B slices shall be allowed or not. 2. In one example, when only slice_type equal to 1_SLICE is allowed (e.g., intra_only_constraint_flag is equal to 1), the value of no_weighted_bipred_constraint_flag shall be equal to 1. x. Weighted predictions for both P slices and B slices are required to be not allowed. 1. A new syntax element (e.g., named no_weighted_pred_constraint_flag) may be signalled in the GCI syntax structure to indicate whether weighted prediction for P and B slices shall be allowed or not. 2. In one example, when only slice_type equal to 1_SLICE is allowed (e.g., intra_only_constraint_flag is equal to 1), the value of no_weighted_pred_constraint_flag shall be equal to 1. xi. SBT is required to be not allowed (e.g., the value of no_sbt_constraint_flag shall be equal to 1). xii. GDR is required to be not allowed (e.g., the value of no_gdr_constraint_flag shall be equal to 1). xiii. A coding tool X which is applied on inter pictures only is not allowed. E.g., the value of a constraint flag no_X_constraint_flag shall be equal to 1. For example, X_flag may be one of: 1. no_ref_wraparound_constraint_flag 2. no_temporal_mvp_constraint_flag 3. no_sbtmvp_constraint_flag 4. no_amvr_constraint_flag 5. no_bdof_constraint_flag 6. no_dmvr_constraint_flag 7. no_affine_motion_constraint_flag 8. no_mmvd_constraint_flag 9. no_smvd_constraint_flag 10. no_prof_constraint_flag 11. no_bcw_constraint_flag 12. no_ciip_constraint_flag 13. no_gpm_constraint_flag b. The SEs in the SPS/PPS/PH/SH may be constrained by the GCI SEs. i. In one example, when each picture only contains one tile (e.g., one_tile_per_pic_constraint_flag is equal to 1), one or more constraints in the following may be specified: 1. The number of tile columns is required to be 1 (e.g., the value of pps_num_exp_tile_columns_minus1 shall be equal to 0). 2. The number of tile rows is required to be 1 (e.g., the value of pps_num_exp_tile_rows_minus1 is inferred to be equal to 0). 3. The slices are required to be rectangular slices other than raster-scan slices (e.g., the value of pps_rect_slice_flag shall be equal to 1). ii. In one example, when APS is required to be not allowed (e.g., no_aps_constraint_flag is equal to 1), one or more constraints in the following may be specified: 1. CCALF is required to be not allowed (e.g., sps_ccalf_enabled_flag shall be equal to 0). 2. The number of ALF luma APS is required to be equal to 1 (e.g., ph_num_alf_aps_ids_luma, slice_num_alf_aps_ids_luma shall be equal to 0). 3. chroma ALF is required to be not allowed (e.g., ph_alf_cb_flag, ph_alf_cr_flag, sh_alf_cb_flag, and sh_alf_cr_flag shall be equal to 0). iii. In one example, when each picture only contains one slice (e.g., one_slice_per_pic_constraint_flag is equal to 1), The slices are required to be rectangular slices other than raster-scan slices (e.g., the value of pps_rect_slice_flag shall be equal to 1). iv. In one example, when each picture only contains one tile and each picture only contains one slice (e.g., one_tile_per_pic_constraint_flag and one_slice_per_pic_constraint flag are both equal to 1), there shall be no picture partition (e.g., the value of pps_no_pic_partition_flag shall be equal to 1). v. In one example, when each picture only contains one slice and the slice is rectangular slice (e.g., one_slice_per_pic_constraint_flag and rect_slice_flag are both equal to 1), then the number of slices in the picture is required to be equal to 1 (e.g., the value of pps_num_slices_in_pic_minus1 shall be equal to 0). vi. In one example, when each picture only contains one subpicture (e.g., one_subpic_per_pic_constraint_flag equal to 1), it specifies that the number of subpictures is required to be equal to 1 (e.g., sps_num_subpics_minus1 shall be equal to 0). c. Some GCI SEs may be constrained by other GCI SEs. i. In one example, when all_layers_independent_constraint_flag is equal to 1, the value of sps_inter_layer_ref_pics_present_flag shall be equal to 0. ii. When no_transform_skip_constraint_flag is equal to 1, the value of no_bdpcm_constraint_flag shall be equal to 1. iii. When no_lmcs_constraint_flag or no_explicit_scaling_list_constraint_flag or no_ccalf_constraint_flag is equal to 0, the value of no_aps_constraint_flag shall be equal to 0. d. The definition of intra_only_constraint_flag considers the nuh_layer_type for each coded slice NAL unit. i. In one example, intra_only_constraint_flag equal to 1 specifies that sh_slice_type shall be equal to 1 and nuh_layer_type for each coded slice NAL unit shall be IDR_N_LP. 16. Whether to signal and/or how to signal/derive the values of a GCI SE may be dependent on profile and/or level information. e. In one example, a GCI SE

may be constrained by profiles and/or levels. i. For example, a GCI SE may be required to be a specific value (e.g. 0 or 1) for a specific profile and/or level. f. In one example, a GCI SE may be conditionally signalled according to profiles and/or levels. i. In one example, the GCI SE is not signalled when the profile and/or level does not satisfy a rule. 1. Alternatively, furthermore, when not present, the GCI SE may be inferred to be a value X (e.g., X being 0 or 1). 2. Alternatively, furthermore, when not present, the GCI SE may be inferred to be a value which is dependent on the profile and/or level. 17. Regarding the `aps_chroma` present flag in case of SCALING APS for solving the 12.sup.th problem, one or more of the following approaches are disclosed: g. The scaling list APS ID could be signalled for luma and chroma, respectively. i. In one example, two syntax elements may be signalled in the PH/SH, to specify the scaling list APS ID for luma and chroma, respectively. ii. In one example, three syntax elements may be signalled in the PH/SH, to specify the scaling list APS ID for each color component, respectively. h. The chroma scaling list may not be signalled even for 4:2:0 and/or 4:2:2 and/or 4:4:4 chroma formats. i. Alternatively, furthermore, default scaling matrix is used for processing chroma components. i. Whether to signal the scaling list SEs for chroma may be dependent on the chroma formats. i. In one example, for 4:0:0 and/or separate-color-plane coding, the chroma scaling list SEs are required to be NOT signalled. ii. In one example, for 4:2:0 and/or 4:2:2 and/or 4:4:4 coding, the chroma scaling list SEs may be or may not be signalled.

6. Embodiments

(82) Below are some example embodiments for some of the aspects summarized above in Section 5, which can be applied to the VVC specification. The changed texts are based on the latest VVC text in JVET-Q2001-vC. Most relevant parts that have been added or modified are highlighted in bold and italicized, and some of the deleted parts are marked with double square brackets (e.g., `[[a]]` denotes the deletion of character “a”).

6.1. First Embodiment

(83) This is an embodiment of items 1, 1.1, 1.1.a, 1.1.b, and 1.1.c summarized above in Section 5.

(84) 6.1.1. Embodiment of Items 2.1 and 2.1a

(85) In one example, the syntax structure `seq_parameter_set_rbsp( )` is changed as follows:

(86) TABLE-US-00050 Descriptor `seq_parameter_set_rbsp( )` { **sps_seq_parameter_set_id** u(4)
sps_video_parameter_set_id u(4) **sps_max_sublayers_minus1** u(3) **sps_reserved_zero_4bits** u(4)
sps_ptl_dpb_hrd_params_present_flag u(1) **if(sps_ptl_dpb_hrd_params_present_flag)**
`profile_tier_level( 1, sps_max_sublayers_minus1 )` **if(!no_gdr_constraint_flag)** **gdr_enabled_flag**
u(1) **if(max_chroma_format_constraint_idc > 0)** **chroma_format_idc** u(2) **if(**
`chroma_format_idc == 3 )` **separate_colour_plane_flag** u(1) **if(**
`!no_res_change_in_clvs_constraint_flag )` **res_change_in_clvs_allowed_flag** u(1)
pic_width_max_in_luma_samples ue(v) **pic_height_max_in_luma_samples** ue(v)
sps_conformance_window_flag u(1) **if(sps_conformance_window_flag)** {
sps_conf_win_left_offset ue(v) **sps_conf_win_right_offset** ue(v) **sps_conf_win_top_offset** ue(v)
sps_conf_win_bottom_offset ue(v) } **sps_log2_ctu_size_minus5** u(2)
subpic_info_present_flag u(1) **if(subpic_info_present_flag)** { **sps_num_subpics_minus1** ue(v)
if(sps_num_subpics_minus1 > 0) **sps_independent_subpics_flag** u(1) **for(i = 0;**
`sps_num_subpics_minus1 > 0 && i <= sps_num_subpics_minus1; i++ )` { **if(i > 0 &&**
`pic_width_max_in_luma_samples > CtbSizeY )` **subpic_ctu_top_left_x[i]** u(v) **if(i >**
`0 && pic_height_max_in_luma_samples > CtbSizeY )` { **subpic_ctu_top_left_y[i]** u(v)
if(i < sps_num_subpics_minus1 && `pic_width_max_in_luma_samples > CtbSizeY )`
subpic_width_minus1[i] u(v) **if(i < sps_num_subpics_minus1 &&**
`pic_height_max_in_luma_samples > CtbSizeY )` **subpic_height_minus1[i]** u(v) **if(**
`!sps_independent_subpics_flag )` { **subpic_treated_as_pic_flag[i]** u(1)
loop_filter_across_subpic_enabled_flag[i] u(1) } } **sps_subpic_id_len_minus1** ue(v)
subpic_id_mapping_explicitly_signalled_flag u(1) **if(subpic_id_mapping_explicitly_signalled_flag)**
{ **subpic_id_mapping_in_sps_flag** u(1) **if(subpic_id_mapping_in_sps_flag)** **for(i = 0;**
`i <= sps_num_subpics_minus1; i++ )` **sps_subpic_id[i]** u(v) } } **if(**
`max_bitdepth_constraint_idc > 0 )` **bit_depth_minus8** ue(v)
sps_entropy_coding_sync_enabled_flag u(1) **if(sps_entropy_coding_sync_enabled_flag)**

```

sps_wpp_entry_point_offsets_present_flag u(1) if( !intra_only_constraint_flag ) {
sps_weighted_pred_flag u(1) sps_weighted_bipred_flag u(1) }
log2_max_pic_order_cnt_lsb_minus4 u(4) sps_poc_msb_flag u(1) if( sps_poc_msb_flag )
poc_msb_len_minus1 ue(v) num_extra_ph_bits_bytes u(2) extra_ph_bits_struct(
num_extra_ph_bits_bytes ) num_extra_sh_bits_bytes u(2) extra_sh_bits_struct(
num_extra_sh_bits_bytes ) if( sps_max_sublayers_minus1 > 0 ) sps_sublayer_dpb_params_flag
u(1) if( sps_ptl_dpb_hrd_params_present_flag ) dpb_parameters( sps_max_sublayers_minus1,
sps_sublayer_dpb_params_flag ) if( !intra_only_constraint_flag ) long_term_ref_pics_flag u(1)
inter_layer_ref_pics_present_flag u(1) if( !intra_only_constraint_flag ) {
sps_idr_rpl_present_flag u(1) rpl1_same_as_rpl0_flag u(1) } for( i = 0; i <
!rpl1_same_as_rpl0_flag ? 2 : 1; i++ ) { num_ref_pic_lists_in_sps[ i ] ue(v) for( j = 0; j <
num_ref_pic_lists_in_sps[ i ]; j++ ) ref_pic_list_struct( i, j ) } if( ChromaArrayType != 0 &&
!no_qtbt_dual_tree_intra_constraint_flag ) qtbt_dual_tree_intra_flag u(1)
log2_min_luma_coding_block_size_minus2 ue(v) if(
!no_partition_constraints_override_constraint_flag ) partition_constraints_override_enabled_flag
u(1) sps_log2_diff_min_qt_min_cb_intra_slice_luma ue(v)
sps_max_mtt_hierarchy_depth_intra_slice_luma ue(v) if(
sps_max_mtt_hierarchy_depth_intra_slice_luma != 0 ) {
sps_log2_diff_max_bt_min_qt_intra_slice_luma ue(v)
sps_log2_diff_max_tt_min_qt_intra_slice_luma ue(v) } sps_log2_diff_min_qt_min_cb_inter_slice
ue(v) sps_max_mtt_hierarchy_depth_inter_slice ue(v) if( sps_max_mtt_hierarchy_depth_inter_slice
!= 0 ) { sps_log2_diff_max_bt_min_qt_inter_slice ue(v)
sps_log2_diff_max_tt_min_qt_inter_slice ue(v) } if( qtbt_dual_tree_intra_flag ) {
sps_log2_diff_min_qt_min_cb_intra_slice_chroma ue(v)
sps_max_mtt_hierarchy_depth_intra_slice_chroma ue(v) if(
sps_max_mtt_hierarchy_depth_intra_slice_chroma != 0 ) {
sps_log2_diff_max_bt_min_qt_intra_slice_chroma ue(v)
sps_log2_diff_max_tt_min_qt_intra_slice_chroma ue(v) } }
sps_max_luma_transform_size_64_flag u(1) if( ChromaArrayType != 0 ) { if(
!no_joint_cbr_constraint_flag ) sps_joint_cbr_enabled_flag u(1)
same_qp_table_for_chroma u(1) numQpTables = same_qp_table_for_chroma ? 1 : (
sps_joint_cbr_enabled_flag ? 3 : 2 ) for( i = 0; i < numQpTables; i++ ) {
qp_table_start_minus26[ i ] se(v) num_points_in_qp_table_minus1[ i ] ue(v) for( j = 0; j
<= num_points_in_qp_table_minus1[ i ]; j++ ) { delta_qp_in_val_minus1[ i ][ j ] ue(v)
delta_qp_diff_val[ i ][ j ] ue(v) } } } if( !no_sao_constraint_flag )
sps_sao_enabled_flag u(1) if( !no_alf_constraint_flag ) sps_alf_enabled_flag u(1) if(
sps_alf_enabled_flag && ChromaArrayType != 0 && !no_ccalf_constraint_flag )
sps_ccalf_enabled_flag u(1) if( !no_transform_skip_constraint_flag )
sps_transform_skip_enabled_flag u(1) if( sps_transform_skip_enabled_flag ) {
log2_transform_skip_max_size_minus2 ue(v) if( !no_bdpcm_constraint_flag )
sps_bdpcm_enabled_flag u(1) } if( !no_ref_wraparound_constraint_flag )
sps_ref_wraparound_enabled_flag u(1) if( !no_temporal_mvp_constraint_flag )
sps_temporal_mvp_enabled_flag u(1) if( sps_temporal_mvp_enabled_flag &&
!no_sbtmvp_constraint_flag ) sps_sbtmvp_enabled_flag u(1) if( !no_amvr_constraint_flag )
sps_amvr_enabled_flag u(1) if( !no_bdof_constraint_flag ) sps_bdof_enabled_flag u(1)
if( sps_bdof_enabled_flag ) sps_bdof_pic_present_flag u(1) sps_smvd_enabled_flag u(1) if(
!no_dmvr_constraint_flag ) sps_dmvr_enabled_flag u(1) if( sps_dmvr_enabled_flag )
sps_dmvr_pic_present_flag u(1) sps_mmvd_enabled_flag u(1) sps_ismvd_enabled_flag u(1)
sps_mrl_enabled_flag u(1) sps_mip_enabled_flag u(1) if( ChromaArrayType != 0 &&
!no_cclm_constraint_flag ) sps_cclm_enabled_flag u(1) if( chroma_format_idc == 1 ) {
sps_chroma_horizontal_collocated_flag u(1) sps_chroma_vertical_collocated_flag u(1) } if(
!no_mts_constraint_flag ) sps_mts_enabled_flag u(1) if( sps_mts_enabled_flag ) {
sps_explicit_mts_intra_enabled_flag u(1) sps_explicit_mts_inter_enabled_flag u(1) }

```

```

six_minus_max_num_merge_cand ue(v) if( !no_sbt_constraint_flag ) sps_sbt_enabled_flag u(1)
    if( !no_affine_motion_constraint_flag ) sps_affine_enabled_flag u(1) if(
sps_affine_enabled_flag ) { five_minus_max_num_subblock_merge_cand ue(v)
sps_affine_type_flag u(1) if( sps_amvr_enabled_flag ) sps_affine_amvr_enabled_flag u(1)
    sps_affine_prof_enabled_flag u(1) if( sps_affine_prof_enabled_flag )
sps_prof_pic_present_flag u(1) } sps_palette_enabled_flag u(1) if( ChromaArrayType == 3
&& !sps_max_luma_transform_size_64_flag ) sps_act_enabled_flag u(1) if(
sps_transform_skip_enabled_flag || sps_palette_enabled_flag ) min_qp_prime_ts_minus4 ue(v)
if( !no_bcw_constraint_flag ) sps_bcw_enabled_flag u(1) if( !no_ibc_constraint_flag )
sps_ibc_enabled_flag u(1) if( sps_ibc_enabled_flag ) six_minus_max_num_ibc_merge_cand
ue(v) if( !no_ciip_constraint_flag ) sps_ciip_enabled_flag u(1) if( sps_mmvd_enabled_flag
&& !no_fpel_mmvd_constraint_flag ) sps_fpel_mmvd_enabled_flag u(1) if(
MaxNumMergeCand >= 2 && !no_gpm_constraint_flag ) { sps_gpm_enabled_flag u(1) if(
sps_gpm_enabled_flag && MaxNumMergeCand >= 3 )
max_num_merge_cand_minus_max_num_gpm_cand ue(v) } if( !no_aps_constraint_flag )
sps_lmcs_enabled_flag u(1) sps_lfnst_enabled_flag u(1) if( !no_ladf_constraint_flag )
sps_ladf_enabled_flag u(1) if( sps_ladf_enabled_flag ) { sps_num_ladf_intervals_minus2 u(2)
    sps_ladf_lowest_interval_qp_offset se(v) for( i = 0; i < sps_num_ladf_intervals_minus2 + 1;
i++ ) { sps_ladf_qp_offset[i ] se(v) sps_ladf_delta_threshold_minus1[i ] ue(v) } }
    log2_parallel_merge_level_minus2 ue(v) if( !no_aps_constraint_flag )
sps_scaling_list_enabled_flag u(1) if( !no_dep_quant_constraint_flag )
sps_dep_quant_enabled_flag u(1) if( !sps_dep_quant_enabled_flag &&
!no_sign_data_hiding_constraint_flag ) sps_sign_data_hiding_enabled_flag u(1)
sps_virtual_boundaries_enabled_flag u(1) if( sps_virtual_boundaries_enabled_flag ) {
sps_virtual_boundaries_present_flag u(1) if( sps_virtual_boundaries_present_flag ) {
sps_num_ver_virtual_boundaries u(2) for( i = 0; i < sps_num_ver_virtual_boundaries; i++ )
    sps_virtual_boundaries_pos_x[ i ] u(13) sps_num_hor_virtual_boundaries u(2)
for( i = 0; i < sps_num_hor_virtual_boundaries; i++ ) sps_virtual_boundaries_pos_y[ i ] u(13)
    } } if( sps_ptl_dpb_hrd_params_present_flag ) { sps_general_hrd_params_present_flag
u(1) if( sps_general_hrd_params_present_flag ) { general_hrd_parameters( ) if(
sps_max_sublayers_minus1 > 0 ) sps_sublayer_cpb_params_present_flag u(1)
firstSubLayer = sps_sublayer_cpb_params_present_flag ? 0 : sps_max_sublayers_minus1
    ols_hrd_parameters( firstSubLayer, sps_max_sublayers_minus1 ) } } field_seq_flag
u(1) vui_parameters_present_flag u(1) if( vui_parameters_present_flag ) vui_parameters( ) /*
Specified in ITU-T H.SEI | ISO/IEC 23002-7 */ sps_extension_flag u(1) if( sps_extension_flag )
    while( more_rbsp_data( ) ) sps_extension_data_flag u(1) rbp_trailing_bits( ) }

```

(87) **gdr_enabled_flag** equal to 1 specifies that GDR pictures may be present in CLVSs referring to the SPS. **gdr_enabled_flag** equal to 0 specifies that GDR pictures are not present in CLVSs referring to the SPS. When not present, the value of **gdr_enabled_flag** is inferred to be equal to 0.

chroma_format_idc specifies the chroma sampling relative to the luma sampling as specified in clause 6.2. **chroma_format_idc** shall be in the range of 0 to **max_chroma_format_constraint_idc**, inclusive. When not present, the value of **chroma_format_idc** is inferred to be equal to 0.

res_change_in_clvs_allowed_flag equal to 1 specifies that the picture spatial resolution may change within a CLVS referring to the SPS. **res_change_in_clvs_allowed_flag** equal to 0 specifies that the picture spatial resolution does not change within any CLVS referring to the SPS. When not present, the value of **res_change_in_clvs_allowed_flag** is inferred to be equal to 0.

bit_depth_minus8 specifies the bit depth of the samples of the luma and chroma arrays, **BitDepth**, and the value of the luma and chroma quantization parameter range offset, **QpBdOffset**, as follows:

BitDepth=8+**bit_depth_minus8** (45)

QpBdOffset=6***bit_depth_minus8** (46)

bit_depth_minus8 shall be in the range of 0 to [[8]] **max_bitdepth_constraint_idc**, inclusive. When not present, the value of **bit_depth_minus8** is inferred to be equal to 0.

sps_weighted_pred_flag equal to 1 specifies that weighted prediction may be applied to P slices referring

sps_sps_weighted_pred_flag equal to 0 specifies that weighted prediction is not applied to P slices referring to the SPS. When not present, the value of sps_weighted_pred_flag is inferred to be equal to 0. sps_weighted_bipred_flag equal to 1 specifies that explicit weighted prediction may be applied to B slices referring to the SPS. sps_weighted_bipred_flag equal to 0 specifies that explicit weighted prediction is not applied to B slices referring to the SPS. When not present, the value of sps_weighted_bipred_flag is inferred to be equal to 0.

long_term_ref_pics_flag equal to 0 specifies that no LTRP is used for inter prediction of any coded picture in the CLVS. long_term_ref_pics_flag equal to 1 specifies that LTRPs may be used for inter prediction of one or more coded pictures in the CLVS. When not present, the value of long_term_ref_pics_flag is inferred to be equal to 0.

inter_layer_ref_pics_present_flag equal to 0 specifies that no ILRP is used for inter prediction of any coded picture in the CLVS. inter_layer_ref_pic_flag equal to 1 specifies that ILRPs may be used for inter prediction of one or more coded pictures in the CLVS. When sps_video_parameter_set_id is equal to 0, the value of inter_layer_ref_pics_present_flag is inferred to be equal to 0. When

vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]] is equal to 1, the value of inter_layer_ref_pics_present_flag shall be equal to 0. When not present, the value of inter_layer_ref_pics_present_flag is inferred to be equal to 0.

sps_idr_rpl_present_flag equal to 1 specifies that reference picture list syntax elements are present in slice headers of IDR pictures. sps_idr_rpl_present_flag equal to 0 specifies that reference picture list syntax elements are not present in slice headers of IDR pictures. When not present, the value of sps_idr_rpl_present_flag is inferred to be equal to 0.

rpl1_same_as_rpl0_flag equal to 1 specifies that the syntax element num_ref_pic_lists_in_sps[1] and the syntax structure ref_pic_list_struct(1, rplIdx) are not present and the following applies: The value of num_ref_pic_lists_in_sps[1] is inferred to be equal to the value of num_ref_pic_lists_in_sps[0]. The value of each of syntax elements in ref_pic_list_struct(1, rplIdx) is inferred to be equal to the value of corresponding syntax element in ref_pic_list_struct(0, rplIdx) for rplIdx ranging from 0 to num_ref_pic_lists_in_sps[0]-1.

When not present, the value of rpl1_same_as_rpl0_flag is inferred to be equal to 0.

partition_constraints_override_enabled_flag equal to 1 specifies the presence of partition_constraints_override_flag in PHs referring to the SPS.

partition_constraints_override_enabled_flag equal to 0 specifies the absence of partition_constraints_override_flag in PHs referring to the SPS. When not present, the value of partition_constraints_override_enabled_flag is inferred to be equal to 0.

sps_sao_enabled_flag equal to 1 specifies that the sample adaptive offset process is applied to the reconstructed picture after the deblocking filter process. sps_sao_enabled_flag equal to 0 specifies that the sample adaptive offset process is not applied to the reconstructed picture after the deblocking filter process. When not present, the value of sps_sao_enabled_flag is inferred to be equal to 0.

sps_alf_enabled_flag equal to 0 specifies that the adaptive loop filter is disabled. sps_alf_enabled_flag equal to 1 specifies that the adaptive loop filter is enabled. When not present, the value of sps_alf_enabled_flag is inferred to be equal to 0.

sps_ccalf_enabled_flag equal to 0 specifies that the cross-component adaptive loop filter is disabled.

sps_ccalf_enabled_flag equal to 1 specifies that the cross-component adaptive loop filter may be enabled. When not present, the value of sps_ccalf_enabled_flag is inferred to be equal to 0.

sps_transform_skip_enabled_flag equal to 1 specifies that transform_skip_flag may be present in the transform unit syntax. sps_transform_skip_enabled_flag equal to 0 specifies that transform_skip_flag is not present in the transform unit syntax. When not present, the value of sps_transform_skip_enabled_flag is inferred to be equal to 0.

sps_ref_wraparound_enabled_flag equal to 1 specifies that horizontal wrap-around motion compensation is applied in inter prediction. sps_ref_wraparound_enabled_flag equal to 0 specifies that horizontal wrap-around motion compensation is not applied. When not present, the value of

sps_ref_wraparound_enabled_flag is inferred to be equal to 0. When the value of

$(CtbSizeY/MinCbSizeY+1)$ is greater than $(pic_width_in_luma_samples/MinCbSizeY-1)$, where

pic_width_in_luma_samples is the value of pic_width_in_luma_samples in any PPS that refers to the SPS,

the value of `sps_ref_wraparound_enabled_flag` shall be equal to 0.

`sps_temporal_mvp_enabled_flag` equal to 1 specifies that temporal motion vector predictors may be used in the CLVS. `sps_temporal_mvp_enabled_flag` equal to 0 specifies that temporal motion vector predictors are not used in the CLVS. When not present, the value of `sps_temporal_mvp_enabled_flag` is inferred to be equal to 0.

`sps_amvr_enabled_flag` equal to 1 specifies that adaptive motion vector difference resolution is used in motion vector coding. `amvr_enabled_flag` equal to 0 specifies that adaptive motion vector difference resolution is not used in motion vector coding. When not present, the value of `sps_amvr_enabled_flag` is inferred to be equal to 0. `sps_bdof_enabled_flag` equal to 0 specifies that the bi-directional optical flow inter prediction is disabled. `sps_bdof_enabled_flag` equal to 1 specifies that the bi-directional optical flow inter prediction is enabled. When not present, the value of `sps_bdof_enabled_flag` is inferred to be equal to 0.

`sps_dmvr_enabled_flag` equal to 1 specifies that decoder motion vector refinement based inter bi-prediction is enabled. `sps_dmvr_enabled_flag` equal to 0 specifies that decoder motion vector refinement based inter bi-prediction is disabled. When not present, the value of `sps_dmvr_enabled_flag` is inferred to be equal to 0.

`sps_mts_enabled_flag` equal to 1 specifies that `sps_explicit_mts_intra_enabled_flag` is present in the sequence parameter set RBSP syntax and `sps_explicit_mts_inter_enabled_flag` is present in the sequence parameter set RBSP syntax. `sps_mts_enabled_flag` equal to 0 specifies that

`sps_explicit_mts_intra_enabled_flag` is not present in the sequence parameter set RBSP syntax and `sps_explicit_mts_inter_enabled_flag` is not present in the sequence parameter set RBSP syntax. When not present, the value of `sps_mts_enabled_flag` is inferred to be equal to 0.

`sps_sbt_enabled_flag` equal to 0 specifies that subblock transform for inter-predicted CUs is disabled.

`sps_sbt_enabled_flag` equal to 1 specifies that subblock transform for inter-predicted CU is enabled. When not present, the value of `sps_sbt_enabled_flag` is inferred to be equal to 0.

`sps_affine_enabled_flag` specifies whether affine model based motion compensation can be used for inter prediction. If `sps_affine_enabled_flag` is equal to 0, the syntax shall be constrained such that no affine model based motion compensation is used in the CLVS, and `inter_affine_flag` and `cu_affine_type_flag` are not present in coding unit syntax of the CLVS. Otherwise (`sps_affine_enabled_flag` is equal to 1), affine model based motion compensation can be used in the CLVS. When not present, the value of `sps_affine_enabled_flag` is inferred to be equal to 0.

`sps_bcw_enabled_flag` specifies whether bi-prediction with CU weights can be used for inter prediction. If `sps_bcw_enabled_flag` is equal to 0, the syntax shall be constrained such that no bi-prediction with CU weights is used in the CLVS, and `bcw_idx` is not present in coding unit syntax of the CLVS. Otherwise (`sps_bcw_enabled_flag` is equal to 1), bi-prediction with CU weights can be used in the CLVS. When not present, the value of `sps_bcw_enabled_flag` is inferred to be equal to 0.

`sps_ciip_enabled_flag` specifies that `ciip_flag` may be present in the coding unit syntax for inter coding units. `sps_ciip_enabled_flag` equal to 0 specifies that `ciip_flag` is not present in the coding unit syntax for inter coding units. When not present, the value of `sps_ciip_enabled_flag` is inferred to be equal to 0.

`sps_fpel_mmvd_enabled_flag` equal to 1 specifies that merge mode with motion vector difference is using integer sample precision. `sps_fpel_mmvd_enabled_flag` equal to 0 specifies that merge mode with motion vector difference can use fractional sample precision. When not present, the value of `sps_fpel_mmvd_enabled_flag` is inferred to be equal to 0.

`sps_lmcs_enabled_flag` equal to 1 specifies that luma mapping with chroma scaling is used in the CLVS.

`sps_lmcs_enabled_flag` equal to 0 specifies that luma mapping with chroma scaling is not used in the CLVS. When not present, the value of `sps_lmcs_enabled_flag` is inferred to be equal to 0.

`sps_lfnst_enabled_flag` equal to 1 specifies that `lfnst_idx` may be present in intra coding unit syntax.

`sps_lfnst_enabled_flag` equal to 0 specifies that `lfnst_idx` is not present in intra coding unit syntax.

`sps_ladf_enabled_flag` equal to 1, specifies that `sps_num_ladf_intervals_minus2`,

`sps_ladf_lowest_interval_qp_offset`, `sps_ladf_qp_offset[i]`, and `sps_ladf_delta_threshold_minus1[i]` are present in the SPS. When not present, the value of `sps_ladf_enabled_flag` is inferred to be equal to 0.

`sps_scaling_list_enabled_flag` equal to 1 specifies that a scaling list is used for the scaling process for transform coefficients. `sps_scaling_list_enabled_flag` equal to 0 specifies that scaling list is not used for

the scaling process for transform coefficients. When not present, the value of

sps_scaling_list_enabled_flag is inferred to be equal to 0.

sps_dep_quant_enabled_flag equal to 0 specifies that dependent quantization is disabled for pictures referring to the SPS. sps_dep_quant_enabled_flag equal to 1 specifies that dependent quantization may be enabled for pictures referring to the SPS. When not present, the value of sps_dep_quant_enabled_flag is inferred to be equal to 0.

6.1.2. Embodiment of Items 2.1 and 2.1b

In one example, the syntax structure picture_header_structure () is changed as follows:

```
(88) TABLE-US-00051 Descriptor picture_header_structure ( ) {   gdr_or_irap_pic_flag   u(1)   if(
gdr_or_irap_pic_flag)       gdr_pic_flag   u(1)   if( !intra_only_constraint_flag )
ph_inter_slice_allowed_flag u(1)   if( ph_inter_slice_allowed_flag)       ph_intra_slice_allowed_flag
u(1)   non_reference_picture_flag   ph_pic_parameter_set_id ue(v)   ph_pic_order_cnt_lsb u(v)
if( gdr_or_irap_pic_flag)       no_output_of_prior_pics_flag u(1) ...   if( rpl_info_in_ph_flag)
ref_pic_lists( ) ...
```

6.1.3. Embodiment of Items 2.1 and 2.1c

In one example, the syntax structure slice_header () is changed as follows:

```
(89) TABLE-US-00052 Descriptor slice_header ( ) {   picture_header_in_slice_header_flag u(1)   if(
picture_header_in_slice_header_flag)       picture_header_structure( )   if( subpic_info_present_flag)
       slice_subpic_id u(v) ...   if( separate_colour_plane_flag == 1 )       colour_plane_id u(2)   if(
!intra_only_constraint_flag && !rpl_info_in_ph_flag && ( ( nal_unit_type != IDR_W_RADL &&
nal_unit_type !=
IDR_N_LP ) || sps_idr_rpl_present_flag ) )       ref_pic_lists( )   if(
!intra_only_constraint_flag && ( rpl_info_in_ph_flag || ( ( nal_unit_type != IDR_W_RADL &&
nal_unit_type !=
IDR_N_LP ) || sps_idr_rpl_present_flag ) ) && ( slice_type != I &&
num_ref_entries[ 0 ][ RplsIdx[ 0 ] ] > 1 ) || ( slice_type == B && num_ref_entries[ 1 ][ RplsIdx[
1 ] ] > 1 ) ) {       num_ref_idx_active_override_flag u(1)       if( num_ref_idx_active_override_flag)
       for( i = 0; i < ( slice_type == B ? 2 : 1 ); i++ )       if( num_ref_entries[ i ][ RplsIdx[ i ] ] > 1 )
       num_ref_idx_active_minus1[ i ] ue(v)   }
```

6.2. Second Embodiment

(90) This is an embodiment of items 3, and 3.1 summarized above in Section 5.

(91) In one example, the general constraint information semantics are changed as follows:

(92) intra_only_constraint_flag equal to 1 specifies that slice_type shall be equal to 1.

intra_only_constraint_flag equal to 0 does not impose such a constraint.

(93) When intra_only_constraint_flag is equal to 1, the value of rpl1_idx_present_flag and num_ref_idx_default_active_minus1[] shall be equal to 0.

(94) one_slice_per_pic_constraint_flag equal to 1 specifies that each picture shall contain only one slice. one_slice_per_pic_constraint_flag equal to 0 does not impose such a constraint.

(95) When one_slice_per_pic_constraint_flag is equal to 1, the value of rect_slice_flag shall be equal to 1.

(96) one_tile_per_pic_constraint_flag equal to 1 specifies that each picture shall contain only one tile. one_tile_per_pic_constraint_flag equal to 0 does not impose such a constraint.

(97) When one_tile_per_pic_constraint flag is equal to 1, the value of num_exp_tile_columns_minus1, num_exp_tile_rows_minus1, rect_slice_flag shall to be equal to 0.

(98) When both one_tile_per_pic_constraint flag and one_slice_per_pic_constraint flag are equal to 1, the value of no_pic_partition_flag shall to be equal to 1.

6.3. Third Embodiment

(99) This is an embodiment of items 4, 4.1, 4.1.a, 4.1.b, and 4.1.c summarized above in Section 5.

(100) 6.3.1. Embodiment of Items 4.1 and 4.1a

(101) In one example, the syntax structure general_constraint_info () is changed as follows:

```
(102) TABLE-US-00053 Descriptor general_constraint_info ( ) {   general_progressive_source_flag
u(1)   general_interlaced_source_flag u(1)   general_non_packed_constraint_flag u(1)
general_frame_only_constraint_flag u(1)   general_non_projected_constraint_flag u(1)
intra_only_constraint_flag u(1)   max_bitdepth_constraint_idc u(4)
max_chroma_format_constraint_idc u(2)   if( !intra_only_constraint_flag)
no_res_change_in_clvs_constraint_flag u(1)   one_tile_per_pic_constraint_flag u(1)
```

```

one_slice_per_pic_constraint_flag u(1)  if ( !one_slice_per_pic_constraint_flag )
one_subpic_per_pic_constraint_flag u(1)  no_qbtt_dual_tree_intra_constraint_flag u(1)
no_partition_constraints_override_constraint_flag u(1)  no_sao_constraint_flag u(1)
no_alf_constraint_flag u(1)  no_ccalf_constraint_flag u(1)  no_joint_cbr_constraint_flag u(1)
if( !intra_only_constraint_flag ) {      no_ref_wraparound_constraint_flag u(1)
no_temporal_mvp_constraint_flag u(1)      no_sbtmvp_constraint_flag u(1)
no_amvr_constraint_flag u(1)      no_bdof_constraint_flag u(1)      no_dmvr_constraint_flag u(1)
 custom character no_cclm_constraint_flag u(1)  no_mts_constraint_flag u(1)  if(
!intra_only_constraint_flag ) {      no_sbt_constraint_flag u(1)      no_affine_motion_constraint_flag
u(1)      no_bcw_constraint_flag u(1)   custom character no_ibc_constraint_flag  if(
!intra_only_constraint_flag )  custom character      no_ciip_constraint_flag u(1)
no_fpel_mmvd_constraint_flag u(1)      no_gpm_constraint_flag u(1)   custom character
no_ladf_constraint_flag u(1)  no_transform_skip_constraint_flag u(1)  if(
!no_transform_skip_constraint_flag )      no_bdpcm_constraint_flag u(1)
no_qp_delta_constraint_flag u(1)  no_dep_quant_constraint_flag u(1)
no_sign_data_hiding_constraint_flag u(1)  if( !intra_only_constraint_flag )  custom character
no_mixed_nalu_types_in_pic_constraint_flag u(1)      no_trail_constraint_flag u(1)
no_stsa_constraint_flag u(1)      no_rasl_constraint_flag u(1)      no_radl_constraint_flag u(1)
 custom character no_idr_constraint_flag u(1)  no_cra_constraint_flag u(1)  if(
!intra_only_constraint_flag )      no_gdr_constraint_flag u(1)  no_aps_constraint_flag u(1)  while(
!byte_aligned( ) )      gci_alignment_zero_bit f(1)  num_reserved_constraint_bytes u(8)  for( i =
0; i < num_reserved_constraint_bytes; i++ )      gci_reserved_constraint_byte[i ] u(8) }

```

6.3.2. Embodiment of Items 4.1 and 4.1b

In one example, the general constraint information semantics are changed as follows:

intra_only_constraint_flag equal to 1 specifies that slice_type shall be equal to 1.

intra_only_constraint_flag equal to 0 does not impose such a constraint.

If intra_only_constraint_flag is equal to 1, the value of no_res_change_in_clvs_constraint_flag, no_ref_wraparound_constraint_flag, no_temporal_mvp_constraint_flag, no_sbtmvp_constraint_flag, no_amvr_constraint_flag, no_bdof_constraint_flag, no_dmvr_constraint_flag, no_sbt_constraint_flag, no_affine_motion_constraint_flag, no_bcw_constraint_flag, no_ciip_constraint_flag, no_fpel_mmvd_constraint_flag, no_gpm_constraint_flag, no_mixed_nalu_types_in_pic_constraint_flag, no_trail_constraint_flag, of no_stsa_constraint_flag, no_rasl_constraint_flag, radl_constraint_flag, no_gdr_constraint_flag shall be equal to 1.

(103) When intra_only_constraint_flag is equal to 1, at least one of the values of no_idr_constraint_flag and no_cra_constraint_flag shall be equal to 0. no_transform_skip_constraint_flag equal to 1 specifies that sps_transform_skip_enabled_flag shall be equal to 0. no_transform_skip_constraint_flag equal to 0 does not impose such a constraint. When no_transform_skip_constraint_flag is equal to 1, the value of no_bdpcm_constraint_flag shall be equal to 1. no_aps_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT present in OlsInScope. no_aps_constraint_flag equal to 0 does not impose such a constraint. When no_aps_constraint_flag is equal to 1, the value of no_alf_constraint_flag shall be equal to 1.

(104) 6.3.3. Embodiment of items 4.1 and 4.1c

(105) In one example, the general constraint information semantics are changed as follows:

(106) max_bitdepth_constraint_idc specifies that bit_depth_minus8 shall be in the range of 0 to max_bitdepth_constraint_idc, inclusive. max_bitdepth_constraint_idc shall be in the range of 0 to 8, inclusive. no_gdr_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to GDR_NUT present in OlsInScope. no_gdr_constraint_flag equal to 0 does not impose such a constraint. At least one of the values of no_gdr_constraint_flag, no_idr_constraint_flag, and no_cra_constraint_flag shall be equal to 0.

6.4. Fourth Embodiment

(107) This is an embodiment of items 5, and 5.a summarized above in Section 5.

(108) In one example, the syntax structure seq_parameter_set_rbsp() is changed as follows:

(109) TABLE-US-00054 Descriptor seq_parameter_set_rbsp() { sps_seq_parameter_set_id u(4) ...

if(!intra_only_constraint_flag) sps_intra_only_flag u(1) . . . if(!sps_intra_only_flag) {
sps_weighted_pred_flag u(1) **sps_weighted_bipred_flag** u(1) } . . . **if(!sps_intra_only_flag)**
 long_term_ref_pics_flag u(1)

sps_intra_only_flag equal to 1 specifies that inter prediction is not allowed within a CLVSs referring to the SPS. sps_intra_only_flag equal to 0 specifies that inter prediction is allowed within a CLVSs referring to the SPS. When not present (in this case the intra_only_constraint_flag is equal to 1), the value of sps_intra_only_flag is inferred to be equal to 1.

And the syntax structure pic_parameter_set_rbsp() is changed as follows:

(110) TABLE-US-00055 Descriptor pic_parameter_set_rbsp() { **pps_pic_parameter_set_id** ue(v)
pps_seq_parameter_set_id u(4) **pps_intra_only_flag** **u(1)** **mixed_nalu_types_in_pic_flag** u(1)
pic_width_in_luma_samples ue(v) **pic_height_in_luma_samples** ue(v) . . . **cabac_init_present_flag**
u(1) **if(!pps_intra_only_flag)**  for(i = 0; i < 2; i++)
num_ref_idx_default_active_minus1[i] ue(v) **rpl1_idx_present_flag** u(1) 
init_qp_minus26 se(v) **cu_qp_delta_enabled_flag** u(1) . . .

And the picture parameter set RBSP semantics are changed as follows:

...

pps_intra_only_flag equal to 1 specifies that each picture referring to the PPS is not allowed to use inter. sps_intra_only_flag equal to 0 specifies that each picture referring to the PPS is allowed to use inter prediction. When sps_intra_only_flag is equal to 1, the value of pps_intra_only_flag shall be equal to 1.

num_ref_idx_default_active_minus1 [i] plus 1, when i is equal to 0, specifies the inferred value of the variable NumRefIdxActive[0] for P or B slices with num_ref_idx_active_override_flag equal to 0, and, when i is equal to 1, specifies the inferred value of NumRefIdxActive[1] for B slices with num_ref_idx_active_override_flag equal to 0. The value of num_ref_idx_default_active_minus1[i] shall be in the range of 0 to 14, inclusive. When not present, the value of num_ref_idx_default_active_minus1[i] shall be equal to 0.

rpl1_idx_present_flag equal to 0 specifies that ref_pic_list_sps_flag[1] and ref_pic_list_idx[1] are not present in the PH syntax structures or the slice headers for pictures referring to the PPS.

rpl1_idx_present_flag equal to 1 specifies that ref_pic_list_sps_flag[1] and ref_pic_list_idx[1] may be present in the PH syntax structures or the slice headers for pictures referring to the PPS. When not present, the value of rpl1_idx_present_flag shall be equal to 0.

...

And the syntax structure picture_header_structure () is changed as follows:

(111) TABLE-US-00056 Descriptor picture_header_structure() { **gdr_or_irap_pic_flag** u(1) if(
gdr_or_irap_pic_flag) **gdr_pic_flag** u(1) **if(!pps_intra_only_flag)**
ph_inter_slice_allowed_flag u(1) if(ph_inter_slice_allowed_flag) **ph_intra_slice_allowed_flag**
u(1) **non_reference_picture_flag** u(1) **ph_pic_parameter_set_id** ue(v) **ph_pic_order_cnt_lsb** u(v)
 if(gdr_or_irap_pic_flag) **no_output_of_prior_pics_flag** u(1)

ph_inter_slice_allowed_flag equal to 0 specifies that all coded slices of the picture have slice_type equal to 2. ph_inter_slice_allowed_flag equal to 1 specifies that there may or may not be one or more coded slices in the picture that have slice_type equal to 0 or 1. When not present, the value of ph_inter_slice_allowed_flag is inferred to be equal to 0.

And the syntax structure slice_header() is changed as follows:

(112) TABLE-US-00057 Descriptor slice_header() { **picture_header_in_slice_header_flag** u(1) if(
picture_header_in_slice_header_flag) picture_header_structure() if(subpic_info_present_flag)
 slice_subpic_id u(v) . . . if(separate_colour_plane_flag == 1) **colour_plane_id** u(2) if(
!pps_intra_only_flag && !rpl_info_in_ph_flag && ((nal_unit_type != IDR_W_RADL &&
nal_unit_type != IDR_N_LP) || sps_idr_rpl_present_flag)) ref_pic_lists() if(
!pps_intra_only_flag && (rpl_info_in_ph_flag || ((nal_unit_type != IDR_W_RADL && nal_unit_type
!= IDR_N_LP) || sps_idr_rpl_present_flag)) && (slice_type != I && num_ref_entries[0][
RplIdx[0]] > 1) || (slice_type == B && num_ref_entries[1][RplIdx[1]] > 1)) {
num_ref_idx_active_override_flag u(1) if(num_ref_idx_active_override_flag) for(i = 0; i <
(slice_type == B ? 2 : 1); i++) if(num_ref_entries[i][RplIdx[i]] > 1)
num_ref_idx_active_minus1[i] ue(v) }

6.5. Fifth Embodiment

(113) This is an embodiment of items 6, and 6.1 summarized above in Section 5.

(114) In one example, the syntax structure seq_parameter_set_rbsp() is changed as follows:

(115) TABLE-US-00058 Descriptor seq_parameter_set_rbsp() { **sps_seq_parameter_set_id** u(4)
 sps_video_parameter_set_id u(4) . . . **if(!no_entropy_coding_sync_constraint_flag)**
 sps_entropy_coding_sync_enabled_flag u(1) **if(!no_wpp_entry_point_offsets_present_constraint_flag**
 && **sps_entropy_coding_sync_enabled_flag)** **sps_wpp_entry_point_offsets_present_flag** u(1) **if(**
 !no_weighted_pred_constraint_flag) **sps_weighted_pred_flag** u(1) **if(**
 !no_weighted_bipred_constraint_flag) **sps_weighted_bipred_flag** u(1)
 log2_max_pic_order_cnt_lsb_minus4 u(4) . . . **if(!no_long_term_ref_pics_constraint_flag)**
 long_term_ref_pics_flag u(1) **if(!no_inter_layer_prediction_constraint_flag)**
 inter_layer_ref_pics_present_flag u(1) . . . **if(!no_max_luma_transform_size_64_constraint_flag)**
 sps_max_luma_transform_size_64_flag u(1) . . . **if(!no_smvd_constraint_flag)**
 sps_smvd_enabled_flag u(1) . . . **if(!no_mvd_constraint_flag)** **sps_mmvd_enabled_flag** u(1) **if(**
 !no_isp_enabled_flag) **sps_isp_enabled_flag** u(1) **if(!no_mrl_enabled_flag)**
 sps_mrl_enabled_flag u(1) **if(!no_mip_constraint_flag)** **sps_mip_enabled_flag** u(1) . . . **if(**
 !no_palette_enabled_flag) **sps_palette_enabled_flag** u(1) **if(!no_act_constrained_flag &&**
 ChromaArrayType == 3 && !sps_max_luma_transform_size_64_flag) **sps_act_enabled_flag** u(1) . .
 . **if(!no_lmcs_constraint_flag)** **sps_lmcs_enabled_flag** u(1) **if(!no_lfnst_constraint_flag)**
 sps_lfnst_enabled_flag u(1) . . . **if(!no_parallel_merge_level_constraint_flag)**
 log2_parallel_merge_level_minus2 ue(v) **if(!no_scaling_list_constraint_flag)**
 sps_scaling_list_enabled_flag u(1) . . . **if(!no_virtual_boundaries_constraint_flag)**
 sps_virtual_boundaries_enabled_flag u(1)

sps_entropy_coding_sync_enabled_flag equal to 1 specifies that a specific synchronization process for context variables is invoked before decoding the CTU that includes the first CTB of a row of CTBs in each tile in each picture referring to the SPS, and a specific storage process for context variables is invoked after decoding the CTU that includes the first CTB of a row of CTBs in each tile in each picture referring to the SPS. sps_entropy_coding_sync_enabled_flag equal to 0 specifies that no specific synchronization process for context variables is required to be invoked before decoding the CTU that includes the first CTB of a row of CTBs in each tile in each picture referring to the SPS, and no specific storage process for context variables is required to be invoked after decoding the CTU that includes the first CTB of a row of CTBs in each tile in each picture referring to the SPS. When not present, the value of sps_entropy_coding_sync_enabled_flag is inferred to be equal to 0.

sps_wpp_entry_point_offsets_present_flag equal to 1 specifies that signalling for entry point offsets for CTU rows may be present in the slice headers of pictures referring to the SPS when

sps_entropy_coding_sync_enabled_flag is equal to 1. sps_wpp_entry_point_offsets_present_flag equal to 0 specifies that signalling for entry point offsets for CTU rows are not present in the slice headers of pictures referring to the SPS. When not present, the value of sps_wpp_entry_point_offsets_present_flag is inferred to be equal to 0.

When not present, the value of sps_wpp_entry_point_offsets_present_flag is inferred to be equal to 0.

sps_weighted_pred_flag equal to 1 specifies that weighted prediction may be applied to P slices referring to the SPS. sps_weighted_pred_flag equal to 0 specifies that weighted prediction is not applied to P slices referring to the SPS. When not present, the value of sps_weighted_pred_flag is inferred to be equal to 0.

sps_weighted_bipred_flag equal to 1 specifies that explicit weighted prediction may be applied to B slices referring to the SPS. sps_weighted_bipred_flag equal to 0 specifies that explicit weighted prediction is not applied to B slices referring to the SPS. When not present, the value of sps_weighted_bipred_flag is inferred to be equal to 0.

long_term_ref_pics_flag equal to 0 specifies that no LTRP is used for inter prediction of any coded picture in the CLVS. long_term_ref_pics_flag equal to 1 specifies that LTRPs may be used for inter prediction of one or more coded pictures in the CLVS. When not present, the value of long_term_ref_pics_flag is inferred to be equal to 0.

inter_layer_ref_pics_present_flag equal to 0 specifies that no ILRP is used for inter prediction of any coded picture in the CLVS. inter_layer_ref_pic_flag equal to 1 specifies that ILRPs may be used for inter

prediction of one or more coded pictures in the CLVS. When `sps_video_parameter_set_id` is equal to 0, the value of `inter_layer_ref_pics_present_flag` is inferred to be equal to 0. When `vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]]` is equal to 1, the value of `inter_layer_ref_pics_present_flag` shall be equal to 0. When not present, the value of `inter_layer_ref_pics_present_flag` is inferred to be equal to 0.

`sps_max_luma_transform_size_64_flag` equal to 1 specifies that the maximum transform size in luma samples is equal to 64. `sps_max_luma_transform_size_64_flag` equal to 0 specifies that the maximum transform size in luma samples is equal to 32. When not present, the value of `sps_max_luma_transform_size_64_flag` is inferred to be equal to 0.

`sps_smvd_enabled_flag` equal to 1 specifies that symmetric motion vector difference may be used in motion vector decoding. `sps_smvd_enabled_flag` equal to 0 specifies that symmetric motion vector difference is not used in motion vector coding. When not present, the value of `sps_smvd_enabled_flag` is inferred to be equal to 0.

`sps_mmvd_enabled_flag` equal to 1 specifies that merge mode with motion vector difference is enabled. `sps_mmvd_enabled_flag` equal to 0 specifies that merge mode with motion vector difference is disabled. When not present, the value of `sps_dmvr_enabled_flag` is inferred to be equal to 0.

`sps_isp_enabled_flag` equal to 1 specifies that intra prediction with subpartitions is enabled. `sps_isp_enabled_flag` equal to 0 specifies that intra prediction with subpartitions is disabled. When not present, the value of `sps_isp_enabled_flag` is inferred to be equal to 0.

`sps_mrl_enabled_flag` equal to 1 specifies that intra prediction with multiple reference lines is enabled. `sps_mrl_enabled_flag` equal to 0 specifies that intra prediction with multiple reference lines is disabled. When not present, the value of `sps_mrl_enabled_flag` is inferred to be equal to 0.

`sps_mip_enabled_flag` equal to 1 specifies that matrix-based intra prediction is enabled. `sps_mip_enabled_flag` equal to 0 specifies that matrix-based intra prediction is disabled. When not present, the value of `sps_mip_enabled_flag` is inferred to be equal to 0.

`sps_palette_enabled_flag` equal to 1 specifies that `pred_mode_plt_flag` may be present in the coding unit syntax. `sps_palette_enabled_flag` equal to 0 specifies that `pred_mode_plt_flag` is not present in the coding unit syntax. When `sps_palette_enabled_flag` is not present, it is inferred to be equal to 0. When not present, the value of `sps_palette_enabled_flag` is inferred to be equal to 0.

`sps_act_enabled_flag` equal to 1 specifies that adaptive color transform may be used and the `cu_act_enabled_flag` may be present in the coding unit syntax. `sps_act_enabled_flag` equal to 0 specifies that adaptive color transform is not used and `cu_act_enabled_flag` is not present in the coding unit syntax. When `sps_act_enabled_flag` is not present, it is inferred to be equal to 0. When not present, the value of `sps_act_enabled_flag` is inferred to be equal to 0.

`sps_lmcs_enabled_flag` equal to 1 specifies that luma mapping with chroma scaling is used in the CLVS. `sps_lmcs_enabled_flag` equal to 0 specifies that luma mapping with chroma scaling is not used in the CLVS. When not present, the value of `sps_lmcs_enabled_flag` is inferred to be equal to 0.

`sps_lfnst_enabled_flag` equal to 1 specifies that `lfnst_idx` may be present in intra coding unit syntax. `sps_lfnst_enabled_flag` equal to 0 specifies that `lfnst_idx` is not present in intra coding unit syntax. When not present, the value of `sps_lfnst_enabled_flag` is inferred to be equal to 0.

`log2_parallel_merge_level_minus2` plus 2 specifies the value of the variable `Log2ParMrgLevel`, which is used in the derivation process for spatial merging candidates as specified in clause 8.5.2.3, the derivation process for motion vectors and reference indices in subblock merge mode as specified in clause 8.5.5.2, and to control the invocation of the updating process for the history-based motion vector predictor list in clause 8.5.2.1. The value of `log2_parallel_merge_level_minus2` shall be in the range of 0 to `CtbLog2SizeY-2`, inclusive. The variable `Log2ParMrgLevel` is derived as follows:

$$\text{Log2ParMrgLevel} = \text{log2_parallel_merge_level_minus2} + 2 \quad (68)$$

When not present, the value of `log2_parallel_merge_level_minus2` is inferred to be equal to 0.

`sps_scaling_list_enabled_flag` equal to 1 specifies that a scaling list is used for the scaling process for transform coefficients. `sps_scaling_list_enabled_flag` equal to 0 specifies that scaling list is not used for the scaling process for transform coefficients. When not present, the value of `sps_scaling_list_enabled_flag` is inferred to be equal to 0.

`sps_virtual_boundaries_present_flag` equal to 1 specifies that information of virtual boundaries is

signalled in the SPS. `sps_virtual_boundaries_present_flag` equal to 0 specifies that information of virtual boundaries is not signalled in the SPS. When there is one or more than one virtual boundaries signalled in the SPS, the in-loop filtering operations are disabled across the virtual boundaries in pictures referring to the SPS. In-loop filtering operations include the deblocking filter, sample adaptive offset filter, and adaptive loop filter operations. When not present, the value of `sps_virtual_boundaries_present_flag` is inferred to be equal to 0.

And the syntax structure `general_constraint_info ( )` is changed as follows:

(116) TABLE-US-00059 Descriptor **general_constraint_info ()** { **general_progressive_source_flag** u(1)

general_interlaced_source_flag **general_non_packed_constraint_flag** u(1)
general_frame_only_constraint_flag u(1) **general_non_projected_constraint_flag** u(1)
intra_only_constraint_flag u(1) **max_bitdepth_constraint_idc** u(4)
max_chroma_format_constraint_idc u(2) **no_entropy_coding_sync_constraint_flag** u(1)
no_wpp_entry_point_offsets_present_constraint_flag u(1) **if(!intra_only_constraint_flag)**
 **custom character** **no_weighted_pred_constraint_flag** u(1)
no_weighted_bipred_constraint_flag u(1) **no_long_term_ref_pics_constraint_flag** u(1)
no_inter_layer_prediction_constraint_flag u(1) **no_res_change_in_clvs_constraint_flag** u(1)
 **custom character** . . . **no_max_luma_transform_size_64_constraint_flag** u(1) . . . **if(**
!intra_only_constraint_flag) { **no_ref_wraparound_constraint_flag** u(1)
no_temporal_mvp_constraint_flag u(1) **no_sbtmvp_constraint_flag** u(1)
no_amvr_constraint_flag u(1) **no_bdof_constraint_flag** u(1) **no_smvd_constraint_flag** u(1)
no_dmvr_constraint_flag u(1) **no_mmvd_constraint_flag** u(1)  **custom character**
no_isp_constraint_flag u(1) **no_mrl_constraint_flag** u(1) **no_mip_constraint_flag** u(1)
no_cclm_constraint_flag u(1) . . . **no_palette_constraint_flag** u(1) **no_act_constraint_flag** u(1)
no_ibc_constraint_flag u(1) . . . **no_lmcs_constraint_flag** u(1) **no_lfst_constraint_flag** u(1)
no_ladf_constraint_flag u(1) **no_transform_skip_constraint_flag** u(1) . . .
no_qp_delta_constraint_flag u(1) **no_parallel_merge_level_constraint_flag** u(1)
no_scaling_list_constraint_flag u(1) **no_dep_quant_constraint_flag** u(1)
no_sign_data_hiding_constraint_flag u(1) **no_virtual_boundaries_constraint_flag** u(1)
intra_only_constraint_flag equal to 1 specifies that `slice_type` shall be equal to 1.

`intra_only_constraint_flag` equal to 0 does not impose such a constraint.

If `intra_only_constraint_flag` is equal to 1, the value of `no_weighted_pred_constraint_flag`,
`no_weighted_bipred_constraint_flag`, `no_long_term_ref_pics_constraint_flag`,
`no_inter_layer_prediction_constraint_flag`, `no_res_change_in_clvs_constraint_flag`,
`no_ref_wraparound_constraint_flag`, `no_temporal_mvp_constraint_flag`, `no_sbtmvp_constraint_flag`,
`no_amvr_constraint_flag`, `no_bdof_constraint_flag`, `no_smvd_constraint_flag`, `no_dmvr_constraint_flag`,
`no_mmvd_constraint_flag`, `no_sbt_constraint_flag`, `no_affine_motion_constraint_flag`,
`no_bcw_constraint_flag`, `no_ciip_constraint_flag`, `no_fpel_mmvd_constraint_flag`,
`no_gpm_constraint_flag`, `no_mixed_nalu_types_in_pic_constraint_flag`, `no_trail_constraint_flag`, of
`no_stsa_constraint_flag`, `no_rasl_constraint_flag`, `radl_constraint_flag`, `no_gdr_constraint_flag` shall be
equal to 1. `no_entropy_coding_sync_constraint_flag` equal to 1 specifies that
`sps_entropy_coding_sync_enabled_flag` is not present. `no_entropy_coding_sync_constraint_flag` equal to
0 specifies that `sps_entropy_coding_sync_enabled_flag` is present.

`no_wpp_entry_point_offsets_present_constraint_flag` equal to 1 specifies that
`sps_wpp_entry_point_offsets_present_flag` is not present.

`no_wpp_entry_point_offsets_present_constraint_flag` equal to 0 specifies that
`sps_wpp_entry_point_offsets_present_flag` is present.

`no_weighted_pred_constraint_flag` equal to 1 specifies that `sps_weighted_pred_flag` is not present.

`no_weighted_pred_constraint_flag` equal to 0 specifies that `sps_weighted_pred_flag` is present.

`no_weighted_bipred_constraint_flag` equal to 1 specifies that `sps_weighted_bipred_flag` is not present.

`no_weighted_bipred_constraint_flag` equal to 0 specifies that `sps_weighted_bipred_flag` is present.

`no_long_term_ref_pics_constraint_flag` equal to 1 specifies that `long_term_ref_pics_flag` is not present.

`no_long_term_ref_pics_constraint_flag` equal to 0 specifies that `long_term_ref_pics_flag` is present.

`no_inter_layer_prediction_constraint_flag` equal to 1 specifies that `inter_layer_ref_pics_present_flag` is

not present. no_inter_layer_prediction_constraint_flag equal to 0 specifies that inter_layer_ref_pics_present_flag is present. When vps_independent_layer_flag[GeneralLayerIdx[nuh_layer_id]] is equal to 1, the value of no_inter_layer_prediction_constraint_flag shall be equal to 1. no_max_luma_transform_size_64_constraint_flag equal to 1 specifies that sps_max_luma_transform_size_64_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_max_luma_transform_size_64_flag is present. no_smvd_constraint_flag equal to 1 specifies that sps_smvd_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_smvd_enabled_flag is present. no_mmvd_constraint_flag equal to 1 specifies that sps_mmvd_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_mmvd_enabled_flag is present. no_isp_constraint_flag equal to 1 specifies that sps_isp_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_isp_enabled_flag is present. no_mrl_constraint_flag equal to 1 specifies that sps_mrl_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_mrl_enabled_flag is present. no_mip_constraint_flag equal to 1 specifies that sps_mip_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_mip_enabled_flag is present. no_palette_constraint_flag equal to 1 specifies that sps_palette_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_palette_enabled_flag is present. no_act_constraint_flag equal to 1 specifies that sps_act_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_act_enabled_flag is present. no_lmcs_constraint_flag equal to 1 specifies that sps_lmcs_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_lmcs_enabled_flag is present. no_lfnst_constraint_flag equal to 1 specifies that sps_lfnst_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_lfnst_enabled_flag is present. no_parallel_merge_level_constraint_flag equal to 1 specifies that log2_parallel_merge_level_minus2 is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that log2_parallel_merge_level_minus2 is present. no_scaling_list_constraint_flag equal to 1 specifies that sps_scaling_list_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_scaling_list_enabled_flag is present. no_virtual_boundaries_constraint_flag equal to 1 specifies that sps_virtual_boundaries_enabled_flag is not present. no_partition_constraints_override_constraint_flag equal to 0 specifies that sps_virtual_boundaries_enabled_flag is present.

6.6. Sixth Embodiment

(117) This is an embodiment of items 7, 7.1, 7.2.c and 7.2.d summarized above in Section 5.

(118) 6.6.1. Embodiment of Items 7.1 and 7.2.c

(119) In one example, the syntax structure adaptation_parameter_set_rbsp () is changed as follows:

(120) TABLE-US-00060 Descriptor adaptation_parameter_set_rbsp () { **adaptation**_parameter_set_id u(5) **aps**_seq_parameter_set_id **u(4)** **aps**_params_type u(3) if(**aps**_params_type == ALF_APS) alf_data () else if(**aps**_params_type == LMCS_APS) lmcs_data () else if(**aps**_params_type == SCALING_APS) scaling_list_data () **aps**_extension_flag u(1) if(**aps**_extension_flag) while(more_rbsp_data ()) **aps**_extension_data_flag u(1) rbsp_trailing_bits () }

aps_seq_parameter_set_id specifies the value of sps_seq_parameter_set_id for the APS. The value of aps_seq_parameter_set_id shall be in the range of 0 to 15, inclusive. The value of aps_seq_parameter_set_id shall be the same in all APSs that are referred to by coded pictures in a CLVS.

And the semantics of adaptive loop filter data are changed as follows:

alf_chroma_filter_signal_flag equal to 1 specifies that a chroma filter is signalled.

alf_chroma_filter_signal_flag equal to 0 specifies that a chroma filter is not signalled. When ChromaArrayType is equal to 0, alf_chroma_filter_signal_flag shall be equal to 0.

When no_aps_constraint_flag is equal to 0 and sps_alf_enabled_flag is equal to 1, at least one of the values of alf_luma_filter_signal_flag, alf_chroma_filter_signal_flag, alf_cc_cb_filter_signal_flag and

alf_cc_cr_filter_signal_flag shall be equal to 1.

6.6.2. Embodiment of Item 7.2.d

In one example, the semantics of adaptive loop filter data are changed as follows:

alf_chroma_filter_signal_flag equal to 1 specifies that a chroma filter is signalled.

alf_chroma_filter_signal_flag equal to 0 specifies that a chroma filter is not signalled. When ChromaArrayType is equal to 0, alf_chroma_filter_signal_flag shall be equal to 0.

If the APS NAL unit having aps_params_type equal to ALF_APS, at least one of the values of alf_luma_filter_signal_flag, alf_chroma_filter_signal_flag, alf_cc_cb_filter_signal_flag and alf_cc_cr_filter_signal_flag shall be equal to 1.

6.7. Seventh Embodiment

(121) Below are some example embodiments for some of the aspects summarized above in Section 5, which can be applied to the VVC specification. The changed texts are based on the latest VVC text in JVET-Q2001-vE. Most relevant parts that have been added or modified are highlighted in bold and italicized, and some of the deleted parts are marked with double square brackets (e.g., [[a]] denotes the deletion of the character “a”).

7.3.2.5 Adaptation Parameter Set RBSP Syntax

(122) TABLE-US-00061 Descriptor adaptation_parameter_set_rbsp() { **adaptation**_parameter_set_id u(5) **aps**_params_type u(3) **aps**_chroma_params_present_flag **u(1)** if(aps_params_type == ALF_APS) alf_data() else if(aps_params_type == LMCS_APS) lmcs_data() else if(aps_params_type == SCALING_APS) scaling_list_data() **aps**_extension_flag u(1) if(aps_extension_flag) while(more_rbsp_data()) **aps**_extension_data_flag u(1) rbsp_trailing_bits() }

aps_chroma_params_present_flag equal to 1 specifies that the APS NAL unit may include chroma information. aps_chroma_params_present_flag equal to 0 specifies that the APS NAL unit does not include chroma information.

7.3.2.19 Adaptive Loop Filter Data Syntax

(123) TABLE-US-00062 Descriptor alf_data() { **alf**_luma_filter_signal_flag u(1) if(aps_chrome_params_present_flag) { **alf**_chroma_filter_signal_flag u(1) **alf**_cc_cb_filter_signal_flag u(1) **alf**_cc_cr_filter_signal_flag u(1) } ... }

7.3.2.20 Luma Mapping with Chroma Scaling Data Syntax

(124) TABLE-US-00063 Descriptor lmcs_data() { **lmcs**_min_bin_idx ue(v) **lmcs**_delta_max_bin_idx ue(v) **lmcs**_delta_cw_prec_minus1 ue(v) for(i = lmcs_min_bin_idx; i <= LmcsMaxBinIdx; i++) { **lmcs**_delta_abs_cw[i] u(v) if(lmcs_delta_abs_cw[i] > 0) **lmcs**_delta_sign_cw_flag[i] u(1) } **if(aps_chrome_params_present_flag)** **lmcs**_delta_abs_crs u(3) if(lmcs_delta_abs_crs > 0) **lmcs**_delta_sign_crs_flag u(1) }

7.3.2.21 Scaling List Data Syntax

(125) TABLE-US-00064 Descriptor scaling_list_data() { **scaling**_matrix_for_lfnst_disabled_flag u(1) [[**scaling**_list_chroma_present_flag]] for(id = 0; id < 28; id ++) matrixSize = (id < 2) ? 2 : ((id < 8) ? 4 : 8) if(aps_chroma_params_present_flag[[scaling_list_chroma_present_flag]] || (id % 3 == 2) || (id == 27)) { **scaling**_list_copy_mode_flag[id] u(1) if(!scaling_list_copy_mode_flag[id]) **scaling**_list_pred_mode_flag[id] u(1) if((scaling_list_copy_mode_flag[id] || scaling_list_pred_mode_flag[id]) && id != 0 && id != 2 && id != 8) **scaling**_list_pred_id_delta[id] ue(v) if(!scaling_list_copy_mode_flag[id]) { nextCoef = 0 if(id > 13) { **scaling**_list_dc_coef[id - 14] se(v) nextCoef += scaling_list_dc_coef[id - 14] } for(i = 0; i < matrixSize * matrixSize; i++) { x = DiagScanOrder[3][3][i][0] y = DiagScanOrder[3][3][i][1] if (!(id > 25 && x >= 4 && y >= 4)) { **scaling**_list_delta_coef[id][i] se(v) nextCoef += scaling_list_delta_coef[id][i] } ScalingList[id][i] = nextCoef } } } } }

And the PH semantics are changed as follows:

...

ph_alf_aps_id_luma[i] specifies the adaptation_parameter_set_id of the i-th ALF APS that the luma component of the slices associated with the PH refers to.

The value of alf_luma_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to ph_alf_aps_id_luma[i] shall be equal to 1.

The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to ph_alf_aps_id_luma[i] shall be less than or equal to the TemporalId of the picture associated with the PH.

The value of aps_chroma_params_present_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to ph_alf_aps_id_luma[i] shall be equal to ChromaArrayType==0?0:1.

...

ph_lmcs_aps_id specifies the adaptation_parameter_set_id of the LMCS APS that the slices associated with the PH refers to. The TemporalId of the APS NAL unit having aps_params_type equal to LMCS_APS and adaptation_parameter_set_id equal to ph_lmcs_aps_id shall be less than or equal to the TemporalId of the picture associated with PH.

The value of aps_chroma_params_present_flag of the APS NAL unit having aps_params_type equal to LMCS_APS and adaptation_parameter_set_id equal to ph_lmcs_aps_id shall be equal to ChromaArrayType==0?0:1.

...

ph_scaling_list_aps_id specifies the adaptation_parameter_set_id of the scaling list APS. The TemporalId of the APS NAL unit having aps_params_type equal to SCALING_APS and adaptation_parameter_set_id equal to ph_scaling_list_aps_id shall be less than or equal to the TemporalId of the picture associated with PH.

The value of aps_chroma_params_present_flag of the APS NAL unit having aps_params_type equal to SCALING_APS and adaptation_parameter_set_id equal to ph_scaling_list_aps_id shall be equal to ChromaArrayType==0?0:1.

And the SH semantics are changed as follows:

slice_alf_aps_id_luma[i] specifies the adaptation_parameter_set_id of the i-th ALF APS that the luma component of the slice refers to. The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_luma[i] shall be less than or equal to the TemporalId of the coded slice NAL unit. When slice_alf_enabled_flag is equal to 1 and slice_alf_aps_id_luma[i] is not present, the value of slice_alf_aps_id_luma[i] is inferred to be equal to the value of ph_alf_aps_id_luma[i].

The value of alf_luma_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_luma[i] shall be equal to 1.

The value of aps_chroma_params_present_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_luma[i] shall be equal to ChromaArrayType==0?0:1.

...

And the ALF data semantics are changed as follows:

...

alf_luma_filter_signal_flag equal to 1 specifies that a luma filter set is signalled.

alf_luma_filter_signal_flag equal to 0 specifies that a luma filter set is not signalled.

alf_chroma_filter_signal_flag equal to 1 specifies that a chroma filter is signalled.

alf_chroma_filter_signal_flag equal to 0 specifies that a chroma filter is not signalled. When not present, the value of alf_chroma_filter_signal_flag is inferred to be equal to 0. [[When ChromaArrayType is equal to 0, alf_chroma_filter_signal_flag shall be equal to 0.]]

alf_cc_cb_filter_signal_flag equal to 1 specifies that cross-component filters for the Cb color component are signalled. alf_cc_cb_filter_signal_flag equal to 0 specifies that cross-component filters for Cb color component are not signalled. When not present, the value of alf_cc_cb_filter_signal_flag is inferred to be equal to 0. [[When ChromaArrayType is equal to 0, alf_cc_cb_filter_signal_flag shall be equal to 0.]]

alf_cc_cr_filter_signal_flag equal to 1 specifies that cross-component filters for the Cr color component are signalled. alf_cc_cr_filter_signal_flag equal to 0 specifies that cross-component filters for the Cr color

component are not signalled. When not present, the value of `alf_cc_cr_filter_signal_flag` is inferred to be equal to 0. [[When `ChromaArrayType` is equal to 0, `alf_cc_cr_filter_signal_flag` shall be equal to 0.]]

...

And the SCALING data semantics are changed as follows:

...

[[`scaling_list_chroma_present_flag` equal to 1 specifies that chroma scaling lists are present in `scaling_list_data()`. `scaling_list_chroma_present_flag` equal to 0 specifies that chroma scaling lists are not present in `scaling_list_data()`. It is a requirement of bitstream conformance that `scaling_list_chroma_present_flag` shall be equal to 0 when `ChromaArrayType` is equal to 0, and shall be equal to 1 when `ChromaArrayType` is not equal to 0.]]

6.8. Eighth Embodiment

(126) Below are some example embodiments for some of the aspects summarized above in Section 5, which can be applied to the VVC specification. The changed texts are based on the latest VVC text in JVET-Q2001-vE. Most relevant parts that have been added or modified are bold and italicized, and some of the deleted parts are marked with double square brackets (e.g., `[[a]]` denotes the deletion of the character “a”).

(127) TABLE-US-00065 Descriptor `adaptation_parameter_set_rbsp()` { **adaptation**_parameter_set_id u(5) **aps**_params_type u(3) **aps**_chroma_present_flag **u(1)** if_aps_params_type == ALF_APS)
 alf_data() else if(aps_params_type == LMCS_APS) lmcs_data() else if(aps_params_type == SCALING_APS) scaling_list_data() **aps**_extension_flag u(1) if(aps_extension_flag) while(more_rbsp_data()) **aps**_extension_data_flag u(1)
 rbsp_trailing_bits() }

(128) TABLE-US-00066 Descriptor `alf_data()` { **alf**_luma_filter_signal_flag u(1) **if** (**aps**_chroma_present_flag) { **alf**_chroma_filter_signal_flag u(1) **alf**_cc_cb_filter_signal_flag u(1) **alf**_cc_cr_filter_signal_flag u(1) } ... }

(129) TABLE-US-00067 Descriptor `lmcs_data()` { ... if (aps_chroma_present_flag)
 lmcs_delta_abs_crs u(3) ... }

(130) TABLE-US-00068 Descriptor `scaling_list_data()` { **scaling**_matrix_for_lfnst_disabled_flag u(1)
 [[scaling_list_chroma_present_flag]] **[[u(1)]]** for(id = 0; id < 28; id ++) matrixSize = (id < 2)
 ? 2 : ((id < 8) ? 4 : 8) if(**[[scaling_list]]** aps_chroma_present_flag || (id % 3 == 2) || (id == 27)) { ... }

7.4.3.1 Picture Header Structure Semantics

...

`ph_alf_aps_id_luma[i]` specifies the `adaptation_parameter_set_id` of the *i*-th ALF APS that the luma component of the slices associated with the PH refers to.

When `ph_alf_aps_id_luma[i]` is present, the following applies: The value of `alf_luma_filter_signal_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_luma[i]` shall be equal to 1. The `TemporalId` of the APS NAL unit having `aps_pamms_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_luma[i]` shall be less than or equal to the `TemporalId` of the picture associated with the PH. When `ChromaArrayType` is equal to 0, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_luma[i]` shall be equal to 0.

`ph_alf_aps_id_chroma` specifies the `adaptation_parameter_set_id` of the ALF APS that the chroma component of the slices associated with the PH refers to.

When `ph_alf_aps_id_chroma` is present, the following applies: The value of `alf_chroma_filter_signal_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_chroma` shall be equal to 1. The `TemporalId` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_chroma` shall be less than or equal to the `TemporalId` of the picture associated with the PH. When `ChromaArrayType` is equal to 1, the value of `aps_chroma_present_flag` of the APS NAL unit having `aps_params_type` equal to `ALF_APS` and `adaptation_parameter_set_id` equal to `ph_alf_aps_id_chroma` shall be equal to 1.

...

ph_cc_alf_cb_aps_id specifies the adaptation_parameter_set_id of the ALF_APS that the Cb color component of the slices associated with the PH refers to.

When ph_cc_alf_cb_aps_id is present, the following applies: The value of alf_cc_cb_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to ph_cc_alf_cb_aps_id shall be equal to 1. The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to ph_cc_alf_cb_aps_id shall be less than or equal to the TemporalId of the picture associated with the PH. When ChromaArrayType is equal to 1, the value of aps_chroma_present_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to ph_cc_alf_cb_aps_id shall be equal to 1.

...

ph_cc_alf_cr_aps_id specifies the adaptation_parameter_set_id of the ALF_APS that the Cr color component of the slices associated with the PH refers to.

When ph_cc_alf_cr_aps_id is present, the following applies: The value of alf_cc_cr_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to ph_cc_alf_cr_aps_id shall be equal to 1. The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to ph_cc_alf_cr_aps_id shall be less than or equal to the TemporalId of the picture associated with the PH. When ChromaArrayType is equal to 1, the value of aps_chroma_present_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to ph_cc_alf_cr_aps_id shall be equal to 1.

...

ph_lmcs_aps_id specifies the adaptation_parameter_set_id of the LMCS APS that the slices associated with the PH refers to.

When ph_lmcs_aps_id is present, the following applies: The TemporalId of the APS NAL unit having aps_params_type equal to LMCS_APS and adaptation_parameter_set_id equal to ph_lmcs_aps_id shall be less than or equal to the TemporalId of the picture associated with PH. The value of aps_chroma_present_flag of the APS NAL unit having aps_params_type equal to LMCS_APS and adaptation_parameter_set_id equal to ph_lmcs_aps_id shall be equal to ChromaArrayType==0?0:1.

...

ph_scaling_list_aps_id specifies the adaptation_parameter_set_id of the scaling list APS.

When ph_scaling_list_aps_id is present, the following applies: The TemporalId of the APS NAL unit having aps_params_type equal to SCALING_APS and adaptation_parameter_set_id equal to ph_scaling_list_aps_id shall be less than or equal to the TemporalId of the picture associated with PH. The value of aps_chroma_present_flag of the APS NAL unit having aps_params_type equal to SCALING_APS and adaptation_parameter_set_id equal to ph_scaling_list_aps_id shall be equal to ChromaArrayType==0?0:1.

7.3.7.1 General Slice Header Semantics

...

slice_alf_aps_id_luma[i] specifies the adaptation_parameter_set_id of the i-th ALF APS that the luma component of the slice refers to. When slice_alf_enabled_flag is equal to 1 and slice_alf_aps_id_luma[i] is not present, the value of slice_alf_aps_id_luma[i] is inferred to be equal to the value of ph_alf_aps_id_luma[i].

When slice_alf_aps_id_luma[i] is present, the following applies: The TemporalId of the APS NAL unit having aps_pamms_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_luma[i] shall be less than or equal to the TemporalId of the coded slice NAL unit. The value of alf_luma_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_luma[i] shall be equal to 1. When ChromaArrayType is equal to 0, the value of aps_chroma_present_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_luma[i] shall be equal to 0.

...

slice_alf_aps_id_chroma specifies the adaptation_parameter_set_id of the ALF APS that the chroma component of the slice refers to. When slice_alf_enabled_flag is equal to 1 and slice_alf_aps_id_chroma is not present, the value of slice_alf_aps_id_chroma is inferred to be equal to the value of

ph_alf_aps_id_chroma.

When slice_alf_aps_id_chroma is present, the following applies: The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_chroma shall be less than or equal to the TemporalId of the coded slice NAL unit. The value of alf_chroma_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_chroma shall be equal to 1. When ChromaArrayType is equal to 1, the value of aps_chroma_present_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_alf_aps_id_chroma shall be equal to 1.

...

slice_cc_alf_cb_aps_id specifies the adaptation_parameter_set_id that the Cb color component of the slice refers to. When slice_cc_alf_cb_enabled_flag is equal to 1 and slice_cc_alf_cb_aps_id is not present, the value of slice_cc_alf_cb_aps_id is inferred to be equal to the value of ph_cc_alf_cb_aps_id.

When slice_cc_alf_cb_aps_id is present, the following applies: The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cb_aps_id shall be less than or equal to the TemporalId of the coded slice NAL unit. The value of alf_cc_cb_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cb_aps_id shall be equal to 1. When ChromaArrayType is equal to 1, the value of aps_chroma_present_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cb_aps_id_chroma shall be equal to 1.

...

slice_cc_alf_cr_aps_id specifies the adaptation_parameter_set_id that the Cr color component of the slice refers to. When slice_cc_alf_cr_enabled_flag is equal to 1 and slice_cc_alf_cr_aps_id is not present, the value of slice_cc_alf_cr_aps_id is inferred to be equal to the value of ph_cc_alf_cr_aps_id.

When slice_cc_alf_cr_aps_id is present, the following applies: The TemporalId of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cr_aps_id shall be less than or equal to the TemporalId of the coded slice NAL unit. The value of alf_cc_cr_filter_signal_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cr_aps_id shall be equal to 1. When ChromaArrayType is equal to 1, the value of aps_chroma_present_flag of the APS NAL unit having aps_params_type equal to ALF_APS and adaptation_parameter_set_id equal to slice_cc_alf_cr_aps_id_chroma shall be equal to 1.

7.4.3.19 Adaptive Loop Filter Data Semantics

alf_chroma_filter_signal_flag equal to 1 specifies that a chroma filter is signalled.

alf_chroma_filter_signal_flag equal to 0 specifies that a chroma filter is not signalled. When [[ChromaArrayType is equal to 0]] not present, alf_chroma_filter_signal_flag is inferred to [[shall]] be equal to 0.

...

alf_cc_cb_filter_signal_flag equal to 1 specifies that cross-component filters for the Cb color component are signalled. alf_cc_cb_filter_signal_flag equal to 0 specifies that cross-component filters for Cb color component are not signalled. When [[ChromaArrayType is equal to 0]] not present, alf_cc_cb_filter_signal_flag is inferred to [[shall]] be equal to 0.

alf_cc_cr_filter_signal_flag equal to 1 specifies that cross-component filters for the Cr color component are signalled. alf_cc_cr_filter_signal_flag equal to 0 specifies that cross-component filters for the Cr color component are not signalled. When [[ChromaArrayType is equal to 0]] not present, alf_cc_cr_filter_signal_flag is inferred to [[shall]] be equal to 0.

7.4.3.21 Scaling List Data Semantics

[[scaling_list]]aps_chroma_present_flag equal to 1 specifies that chroma data related to ALF, LMCS and scaling lists are present respectively in alf_data, lmcs_data and scaling_list_data().

[[scaling_list]]aps_chroma_present_flag equal to 0 specifies that chroma data related to ALF, LMCS and scaling lists are not present respectively in alf_data, lmcs_data and scaling_list_data(). [[It is a requirement of bitstream conformance that scaling_list_chroma_present_flag shall be equal to 0 when

ChromaArrayType is equal to 0, and shall be equal to 1 when ChromaArrayType is not equal to 0.]]

6.1. Ninth Embodiment

(131) Below are some example embodiments for some of the aspects summarized above in Section 5, which can be applied to the VVC specification. The changed texts are based on the latest VVC text in JVET-R2001-vA. Most relevant parts that have been added or modified are highlighted in bold and italicized, and some of the deleted parts are marked with double square brackets (e.g., [[a]] denotes the deletion of the character “a”).

7.3.3 Profile, Tier, and Level Syntax

7.3.3.1 General Profile, Tier, and Level Syntax

(132) TABLE-US-00069 Descriptor profile_tier_level(profileTierPresentFlag, maxNumSubLayersMinus1) { if(profileTierPresentFlag) { **general_profile_idc** u(7) **general_tier_flag** u(1) **gci_present_flag** u(1) **if(gci_present_flag)** general_constraint_info() **while(!byte_aligned())** **ptl_alignment_zero_bit** f(1) } **general_level_idc** u(8) if(profileTierPresentFlag) { **ptl_num_sub_profiles** u(8) for(i = 0; i < ptl_num_sub_profiles; i++) **general_sub_profile_idc**[i] u(32) } for(i = 0; i < maxNumSubLayersMinus1; i++) **ptl_sublayer_level_present_flag**[i] u(1) while(!byte_aligned()) **ptl_alignment_zero_bit** f(1) for i = 0; i < maxNumSubLayersMinus1; i++) if(**ptl_sublayer_level_present_flag**[i]) **sublayer_level_idc**[i] u(8) } gci_present_flag equal to 1 specifies that the general_constraint_info() syntax structure is present in the profile_tier_level() syntax structure when profileTierPresentFlag is equal to 1. gci_present_flag equal to 0 specifies that the general_constraint_info() syntax structure is not present in the profile_tier_level() syntax structure.

When gci_present_flag equal to 0 for a profile_tier_level() syntax structure with profileTierPresentFlag equal to 1, the value of max_bitdepth_constraint_idc is inferred to be equal to 8, the value of max_chroma_format_constraint_idc is inferred to be equal to 3, and the value of the each of the other syntax elements in the general_constraint_info() syntax structure starting from general_non_packed_constraint_flag to no_aps_constraint_flag, inclusive, except is inferred to be equal to 0. ptl_alignment_zero_bit shall be equal to 0.

...

7.3.3.2 General Constraint Information Syntax

(133) TABLE-US-00070 Descriptor general_constraint_info() { **general_non_packed_constraint_flag** u(1) **general_frame_only_constraint_flag** u(1) **general_non_projected_constraint_flag** u(1) **general_one_picture_only_constraint_flag** u(1) **intra_only_constraint_flag** u(1) **max_bitdepth_constraint_idc** u(4) **max_chroma_format_constraint_idc** u(2) **single_layer_constraint_flag** u(1) **all_layers_independent_constraint_flag** u(1) **no_ref_pic_resampling_constraint_flag** u(1) **no_res_change_in_clvs_constraint_flag** u(1) **one_tile_per_pic_constraint_flag** u(1) **pic_header_in_slice_header_constraint_flag** u(1) **one_slice_per_pic_constraint_flag** u(1) **one_subpic_per_pic_constraint_flag** u(1) **no_qtbt_dual_tree_intra_constraint_flag** u(1) **no_partition_constraints_override_constraint_flag** u(1) **no_sao_constraint_flag** u(1) **no_alf_constraint_flag** u(1) **no_ccalf_constraint_flag** u(1) **no_joint_cbr_constraint_flag** u(1) **no_mrl_constraint_flag** u(1) **no_isp_constraint_flag** u(1) **no_mip_constraint_flag** u(1) **no_weighted_pred_constraint_flag** u(1) **no_weighted_bipred_constraint_flag** u(1) **no_ref_wraparound_constraint_flag** u(1) **no_temporal_mvp_constraint_flag** u(1) **no_sbtmvp_constraint_flag** u(1) **no_amvr_constraint_flag** u(1) **no_bdof_constraint_flag** u(1) **no_dmv_constraint_flag** u(1) **no_cclm_constraint_flag** u(1) **no_mts_constraint_flag** u(1) **no_sbt_constraint_flag** u(1) **no_lfnst_constraint_flag** u(1) **no_explicit_scaling_list_constraint_flag** u(1) **no_affine_motion_constraint_flag** u(1) **no_mmvd_constraint_flag** u(1) **no_smvd_constraint_flag** u(1) **no_prof_constraint_flag** u(1) **no_bcw_constraint_flag** u(1) **no_ibc_constraint_flag** u(1) **no_ciip_constraint_flag** u(1) **no_gpm_constraint_flag** u(1) **no_ladf_constraint_flag** u(1) **no_transform_skip_constraint_flag** u(1) **no_bdpcm_constraint_flag** u(1) **no_palette_constraint_flag** u(1) **no_act_constraint_flag** u(1) **no_lmcs_constraint_flag** u(1) **no_cu_qp_delta_constraint_flag** u(1) **no_chroma_qp_offset_constraint_flag** u(1) **no_dep_quant_constraint_flag** u(1)

```

no_sign_data_hiding_constraint_flag u(1)    no_virtual_boundaries_constraint_flag u(1)
no_tsrc_constraint_flag u(1)    no_mixed_nalu_types_in_pic_constraint_flag u(1)
no_trail_constraint_flag u(1)    no_stsa_constraint_flag u(1)    no_rasl_constraint_flag u(1)
no_radl_constraint_flag u(1)    no_idr_constraint_flag u(1)    no_cra_constraint_flag u(1)
no_gdr_constraint_flag u(1)    no_aps_constraint_flag u(1) [[ while( !byte_aligned( ) )]]
[[gci_alignment_zero_bit]] [[f(1)]    gci_num_reserved_b[[ytes]]its u([[8]]11)    for( i = 0; i <
gci_num_reserved_b[[ytes]]its; i++ )    gci_reserved_b[[yte]]it [ i ] u([[8]]1) }

```

7.4.4.2 General Constraint Information Semantics

...

intra_only_constraint_flag equal to 1 specifies that sh_slice_type shall be equal to 1 and nuh_layer_type for each coded slice NAL unit shall be IDR_N_LP. intra_only_constraint_flag equal to 0 does not impose such a constraint. When general_one_picture_only_constraint_flag is equal to 1, the value of intra_only_constraint_flag shall be equal to 1. When intra_only_constraint_flag is equal to 1, the value of long_term_ref_pics_flag, sps_idr_rpl_present_flag, sps_num_ref_pic_lists[i], pps_rpl_info_in_ph_flag shall be equal to 0.

max_bitdepth_constraint_idc specifies that sps_bit_depth_minus8 shall be in the range of 0 to max_bitdepth_constraint_idc, inclusive. The value of max_bitdepth_constraint_idc is required to be in the range of 0 to 8, inclusive.

max_chroma_format_constraint_idc specifies that sps_chroma_format_idc shall be in the range of 0 to max_chroma_format_constraint_idc, inclusive.

single_layer_constraint_flag equal to 1 specifies that sps_video_parameter_set_id shall be equal to 0.

single_layer_constraint_flag equal to 0 does not impose such a constraint. When general_one_picture_only_constraint_flag is equal to 1, the value of single_layer_constraint_flag shall be equal to 1.

all_layers_independent_constraint_flag equal to 1 specifies that vps_all_independent_layers_flag shall be equal to 1. all_layers_independent_constraint_flag equal to 0 does not impose such a constraint. When all_layers_independent_constraint_flag is equal to 1, the value of sps_inter_layer_ref_pics_present_flag shall be equal to 0. When intra_only_constraint_flag is equal to 1, the value of all_layers_independent_constraint_flag shall be equal to 1.

no_ref_pic_resampling_constraint_flag equal to 1 specifies that sps_ref_pic_resampling_enabled_flag shall be equal to 0. no_ref_pic_resampling_constraint_flag equal to 0 does not impose such a constraint. When intra_only_constraint_flag is equal to 1, the value of no_ref_pic_resampling_constraint_flag shall be equal to 1.

no_res_change_in_clvs_constraint_flag equal to 1 specifies that sps_res_change_in_clvs_allowed_flag shall be equal to 0. no_res_change_in_clvs_constraint_flag equal to 0 does not impose such a constraint. When intra_only_constraint_flag is equal to 1, the value of no_res_change_in_clvs_constraint_flag shall be equal to 1.

one_tile_per_pic_constraint_flag equal to 1 specifies that each picture shall contain only one tile, i.e., the value of NumTilesInPic that applies to each picture shall be equal to 1. one_tile_per_pic_constraint_flag equal to 0 does not impose such a constraint. When one_tile_per_pic_constraint_flag is equal to 1, the value of pps_num_exp_tile_columns_minus1, pps_num_exp_tile_rows_minus1, pps_rect_slice_flag shall be equal to 0.

When one_tile_per_pic_constraint_flag and one_slice_per_pic_constraint_flag are both equal to 1, the value of pps_no_pic_partition_flag shall be equal to 1.

pic_header_in_slice_header_constraint_flag equal to 1 specifies that each picture shall contain only one slice and the value of sh_picture_header_in_slice_header_flag in each slice shall be equal to 1.

pic_header_in_slice_header_constraint_flag equal to 0 does not impose such a constraint.

one_slice_per_pic_constraint_flag equal to 1 specifies that each picture shall contain only one slice, i.e., if pps_rect_slice_flag is equal to 1, pps_num_slices_in_pic_minus1 shall be equal to 0, otherwise, the value of num_tiles_in_slice_minus1 present in each slice header shall be equal to NumTilesInPic-1.

one_slice_per_pic_constraint_flag equal to 0 does not impose such a constraint. When

one_slice_per_pic_constraint_flag is equal to 1, the value of pps_rect_slice_flag shall be equal to 1. When pic_header_in_slice_header_constraint_flag is equal to 1, the value of one_slice_per_pic_constraint_flag

shall be equal to 1.

one_subpic_per_pic_constraint_flag equal to 1 specifies that [[each picture shall contain only one subpicture]] the value of sps_num_subpics_minus1 shall be equal to 0.

one_subpic_per_pic_constraint_flag equal to 0 does not impose such a constraint. When

one_slice_per_pic_constraint_flag is equal to 1, the value of one_subpic_per_pic_constraint_flag shall be equal to 1.

...

no_weighted_pred_constraint_flag equal to 1 specifies that sps_weighted_pred_flag shall be equal to 0.

no_weighted_pred_constraint_flag equal to 0 does not impose such a constraint. When

intra_only_constraint_flag is equal to 1, the value of no_weighted_pred_constraint_flag shall be equal to 1.

no_weighted_bipred_constraint_flag equal to 1 specifies that sps_weighted_bipred_flag shall be equal to 0. no_weighted_bipred_constraint_flag equal to 0 does not impose such a constraint. When

intra_only_constraint_flag is equal to 1, the value of no_weighted_bipred_constraint_flag shall be equal to 1.

...

no_sbt_constraint_flag equal to 1 specifies that sps_sbt_enabled_flag shall be equal to 0.

no_sbt_constraint_flag equal to 0 does not impose such a constraint. When intra_only_constraint_flag is equal to 1, the value of no_sbt_constraint_flag shall be equal to 1.

...

no_transform_skip_constraint_flag equal to 1 specifies that sps_transform_skip_enabled_flag shall be equal to 0. no_transform_skip_constraint_flag equal to 0 does not impose such a constraint.

no_bdpcm_constraint_flag equal to 1 specifies that sps_bdpcm_enabled_flag shall be equal to 0.

no_bdpcm_constraint_flag equal to 0 does not impose such a constraint. When

no_transform_skip_constraint_flag is equal to 1, the value of no_bdpcm_constraint_flag shall be equal to 1.

no_palette_constraint_flag equal to 1 specifies that sps_palette_enabled_flag shall be equal to 0.

no_palette_constraint_flag equal to 0 does not impose such a constraint.

no_act_constraint_flag equal to 1 specifies that sps_act_enabled_flag shall be equal to 0.

no_act_constraint_flag equal to 0 does not impose such a constraint.

no_lmcs_constraint_flag equal to 1 specifies that sps_lmcs_enabled_flag shall be equal to 0.

no_lmcs_constraint_flag equal to 0 does not impose such a constraint.

no_explicit_scaling_list_constraint_flag equal to 1 specifies that sps_explicit_scaling_list_enabled_flag shall be equal to 0. no_explicit_scaling_list_constraint_flag equal to 0 does not impose such a constraint.

no_cu_qp_delta_constraint_flag equal to 1 specifies that pps_cu_qp_delta_enabled_flag shall be equal to 0. no_cu_qp_delta_constraint_flag equal to 0 does not impose such a constraint.

no_chroma_qp_offset_constraint_flag equal to 1 specifies that

pps_cu_chroma_qp_offset_list_enabled_flag shall be equal to 0. no_chroma_qp_offset_constraint_flag equal to 0 does not impose such a constraint.

no_dep_quant_constraint_flag equal to 1 specifies that sps_dep_quant_enabled_flag shall be equal to 0.

no_dep_quant_constraint_flag equal to 0 does not impose such a constraint.

no_sign_data_hiding_constraint_flag equal to 1 specifies that sps_sign_data_hiding_enabled_flag shall be equal to 0. no_sign_data_hiding_constraint_flag equal to 0 does not impose such a constraint.

no_virtual_boundaries_constraint_flag equal to 1 specifies that sps_virtual_boundaries_enabled_flag shall be equal to 0. no_virtual_boundaries_constraint_flag equal to 0 does not impose such a constraint.

...

no_idr_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to IDR_W_RADL or IDR_N_LP present in OlsInScope. no_idr_constraint_flag equal to 0 does not impose such a constraint.

no_cra_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to CRA_NUT present in OlsInScope. no_cra_constraint_flag equal to 0 does not impose such a constraint.

When intra_only_constraint_flag is equal to 1, at least one of the values of no_idr_constraint_flag and no_cra_constraint_flag shall be equal to 0.

no_gdr_constraint_flag equal to 1 specifies that sps_gdr_enabled_flag shall be equal to 0.
no_gdr_constraint_flag equal to 0 does not impose such a constraint. When intra_only_constraint_flag is equal to 1, the value of no_gdr_constraint_flag shall be equal to 1.

At least one of the values of no_gdr_constraint_flag, no_idr_constraint_flag, and no_cra_constraint_flag shall be equal to 0.

no_aps_constraint_flag equal to 1 specifies that there shall be no NAL unit with nuh_unit_type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT present in OlsInScope, and sps_lmcs_enabled_flag, sps_explicit_scaling_list_enabled_flag, sps_ccalf_enabled_flag, ph_num_alf_aps_ids_luma, slice_num_alf_aps_ids_luma, ph_alf_cb_flag, ph_alf_cr_flag, sh_alf_cb_flag, and sh_alf_cr_flag shall [[both]] all be equal to 0. no_aps_constraint_flag equal to 0 does not impose such a constraint. When no_lmcs_constraint_flag or no_explicit_scaling_list_constraint_flag or no_ccalf_constraint_flag is equal to 0, the value of no_aps_constraint_flag shall be equal to 0.

[[gci_alignment_zero_bits shall be equal to 0.]]

gci_num_reserved_b[[ytes]]its specifies the number of the reserved constraint b[[ytes]]its. The value of gci_num_reserved_b[[ytes]]its shall be 0. Other values of gci_num_reserved_b[[ytes]]its are reserved for future use by ITU-T|ISO/IEC and shall not be present in bitstreams conforming to this version of this Specification.

gci_reserved_b[[yte]]it[i] may have any value. Its presence and value do not affect decoder conformance to profiles specified in this version of this Specification. Decoders conforming to this version of this Specification shall ignore the values of all the gci_reserved_b[[yte]]it[i] syntax elements.

(134) FIG. 1 is a block diagram showing an example video processing system **1900** in which various embodiments disclosed herein may be implemented. Various embodiments may include some or all of the components of the system **1900**. The system **1900** may include input **1902** for receiving video content. The video content may be received in a raw or uncompressed format, e.g., 8- or 10-bit multi-component pixel values, or may be in a compressed or encoded format. The input **1902** may represent a network interface, a peripheral bus interface, or a storage interface. Examples of network interface include wired interfaces such as Ethernet, passive optical network (PON), etc. and wireless interfaces such as Wi-Fi or cellular interfaces.

(135) The system **1900** may include a coding component **1904** that may implement the various coding or encoding methods described in the present disclosure. The coding component **1904** may reduce the average bitrate of video from the input **1902** to the output of the coding component **1904** to produce a coded representation of the video. The coding techniques are therefore sometimes called video compression or video transcoding techniques. The output of the coding component **1904** may be either stored, or transmitted via a communication connected, as represented by the component **1906**. The stored or communicated bitstream (or coded) representation of the video received at the input **1902** may be used by the component **1908** for generating pixel values or displayable video that is sent to a display interface **1910**. The process of generating user-viewable video from the bitstream representation is sometimes called video decompression. Furthermore, while certain video processing operations are referred to as “coding” operations or tools, it will be appreciated that the coding tools or operations are used at an encoder and corresponding decoding tools or operations that reverse the results of the coding will be performed by a decoder.

(136) Examples of a peripheral bus interface or a display interface may include universal serial bus (USB) or high definition multimedia interface (HDMI) or DisplayPort, and so on. Examples of storage interfaces include serial advanced technology attachment (SATA), peripheral component interface (PCI), integrated drive electronics (IDE) interface, and the like. The embodiments described in the present disclosure may be embodied in various electronic devices such as mobile phones, laptops, smartphones or other devices that are capable of performing digital data processing and/or video display.

(137) FIG. 2 is a block diagram of a video processing apparatus **3600**. The apparatus **3600** may be used to implement one or more of the methods described herein. The apparatus **3600** may be embodied in a smartphone, tablet, computer, Internet of Things (IoT) receiver, and so on. The apparatus **3600** may include one or more processors **3602**, one or more memories **3604** and video processing hardware **3606**. The processor(s) **3602** may be configured to implement one or more methods described in the present disclosure. The memory (memories) **3604** may be used for storing data and code used for implementing

the methods and embodiments described herein. The video processing hardware **3606** may be used to implement, in hardware circuitry, some embodiments described in the present disclosure.

(138) FIG. **4** is a block diagram that illustrates an example video coding system **100** that may utilize the embodiments of this disclosure.

(139) As shown in FIG. **4**, video coding system **100** may include a source device **110** and a destination device **120**. Source device **110** generates encoded video data which may be referred to as a video encoding device. Destination device **120** may decode the encoded video data generated by source device **110** which may be referred to as a video decoding device.

(140) Source device **110** may include a video source **112**, a video encoder **114**, and an input/output (I/O) interface **116**.

(141) Video source **112** may include a source such as a video capture device, an interface to receive video data from a video content provider, and/or a computer graphics system for generating video data, or a combination of such sources. The video data may comprise one or more pictures. Video encoder **114** encodes the video data from video source **112** to generate a bitstream. The bitstream may include a sequence of bits that form a coded representation of the video data. The bitstream may include coded pictures and associated data. The coded picture is a coded representation of a picture. The associated data may include sequence parameter sets, picture parameter sets, and other syntax structures. I/O interface **116** may include a modulator/demodulator (modem) and/or a transmitter. The encoded video data may be transmitted directly to destination device **120** via I/O interface **116** through network **130a**. The encoded video data may also be stored onto a storage medium/server **130b** for access by destination device **120**.

(142) Destination device **120** may include an I/O interface **126**, a video decoder **124**, and a display device **122**.

(143) I/O interface **126** may include a receiver and/or a modem. I/O interface **126** may acquire encoded video data from the source device **110** or the storage medium/server **130b**. Video decoder **124** may decode the encoded video data. Display device **122** may display the decoded video data to a user. Display device **122** may be integrated with the destination device **120**, or may be external to destination device **120** which be configured to interface with an external display device.

(144) Video encoder **114** and video decoder **124** may operate according to a video compression standard, such as the High Efficiency Video Coding (HEVC) standard, Versatile Video Coding (VVC) standard and other current and/or further standards.

(145) FIG. **5** is a block diagram illustrating an example of video encoder **200**, which may be video encoder **114** in the system **100** illustrated in FIG. **4**.

(146) Video encoder **200** may be configured to perform any or all of the embodiments of this disclosure. In the example of FIG. **5**, video encoder **200** includes a plurality of functional components. The embodiments described in this disclosure may be shared among the various components of video encoder **200**. In some examples, a processor may be configured to perform any or all of the embodiments described in this disclosure.

(147) The functional components of video encoder **200** may include a partition unit **201**, a prediction unit **202** which may include a mode select unit **203**, a motion estimation unit **204**, a motion compensation unit **205**, and an intra prediction unit **206**; a residual generation unit **207**; a transform unit **208**; a quantization unit **209**; an inverse quantization unit **210**; an inverse transform unit **211**; a reconstruction unit **212**; a buffer **213**; and an entropy encoding unit **214**.

(148) In other examples, video encoder **200** may include more, fewer, or different functional components. In an example, prediction unit **202** may include an intra block copy (IBC) unit. The IBC unit may perform prediction in an IBC mode in which at least one reference picture is a picture where the current video block is located.

(149) Furthermore, some components, such as motion estimation unit **204** and motion compensation unit **205** may be highly integrated, but are represented in the example of FIG. **5** separately for purposes of explanation.

(150) Partition unit **201** may partition a picture into one or more video blocks. Video encoder **200** and video decoder **300** may support various video block sizes.

(151) Mode select unit **203** may select one of the coding modes, intra or inter, e.g., based on error results, and provide the resulting intra- or inter-coded block to a residual generation unit **207** to generate residual

block data and to the reconstruction unit **212** to reconstruct the encoded block for use as a reference picture. In some examples, mode select unit **203** may select a combination of intra and inter prediction (CIIP) mode in which the prediction is based on an inter prediction signal and an intra prediction signal. Mode select unit **203** may also select a resolution for a motion vector (e.g., a sub-pixel or integer pixel precision) for the block in the case of inter-prediction.

(152) To perform inter prediction on a current video block, motion estimation unit **204** may generate motion information for the current video block by comparing one or more reference frames from buffer **213** to the current video block. Motion compensation unit **205** may determine a predicted video block for the current video block based on the motion information and decoded samples of pictures from buffer **213** other than the picture associated with the current video block.

(153) Motion estimation unit **204** and motion compensation unit **205** may perform different operations for a current video block, for example, depending on whether the current video block is in an I slice, a P slice, or a B slice.

(154) In some examples, motion estimation unit **204** may perform uni-directional prediction for the current video block, and motion estimation unit **204** may search reference pictures of list 0 or list 1 for a reference video block for the current video block. Motion estimation unit **204** may then generate a reference index that indicates the reference picture in list 0 or list 1 that contains the reference video block and a motion vector that indicates a spatial displacement between the current video block and the reference video block. Motion estimation unit **204** may output the reference index, a prediction direction indicator, and the motion vector as the motion information of the current video block. Motion compensation unit **205** may generate the predicted video block of the current block based on the reference video block indicated by the motion information of the current video block.

(155) In other examples, motion estimation unit **204** may perform bi-directional prediction for the current video block, motion estimation unit **204** may search the reference pictures in list 0 for a reference video block for the current video block and may also search the reference pictures in list 1 for another reference video block for the current video block. Motion estimation unit **204** may then generate reference indexes that indicate the reference pictures in list 0 and list 1 containing the reference video blocks and motion vectors that indicate spatial displacements between the reference video blocks and the current video block. Motion estimation unit **204** may output the reference indexes and the motion vectors of the current video block as the motion information of the current video block. Motion compensation unit **205** may generate the predicted video block of the current video block based on the reference video blocks indicated by the motion information of the current video block.

(156) In some examples, motion estimation unit **204** may output a full set of motion information for decoding processing of a decoder.

(157) In some examples, motion estimation unit **204** may not output a full set of motion information for the current video. Rather, motion estimation unit **204** may signal the motion information of the current video block with reference to the motion information of another video block. For example, motion estimation unit **204** may determine that the motion information of the current video block is sufficiently similar to the motion information of a neighboring video block.

(158) In one example, motion estimation unit **204** may indicate, in a syntax structure associated with the current video block, a value that indicates to the video decoder **300** that the current video block has the same motion information as the another video block.

(159) In another example, motion estimation unit **204** may identify, in a syntax structure associated with the current video block, another video block and a motion vector difference (MVD). The motion vector difference indicates a difference between the motion vector of the current video block and the motion vector of the indicated video block. The video decoder **300** may use the motion vector of the indicated video block and the motion vector difference to determine the motion vector of the current video block.

(160) As discussed above, video encoder **200** may predictively signal the motion vector. Two examples of predictive signalling techniques that may be implemented by video encoder **200** include advanced motion vector prediction (AMVP) and merge mode signalling.

(161) Intra prediction unit **206** may perform intra prediction on the current video block. When intra prediction unit **206** performs intra prediction on the current video block, intra prediction unit **206** may generate prediction data for the current video block based on decoded samples of other video blocks in the

same picture. The prediction data for the current video block may include a predicted video block and various syntax elements.

(162) Residual generation unit **207** may generate residual data for the current video block by subtracting (e.g., indicated by the minus sign) the predicted video block(s) of the current video block from the current video block. The residual data of the current video block may include residual video blocks that correspond to different sample components of the samples in the current video block.

(163) In other examples, there may be no residual data for the current video block for the current video block, for example in a skip mode, and residual generation unit **207** may not perform the subtracting operation.

(164) Transform processing unit **208** may generate one or more transform coefficient video blocks for the current video block by applying one or more transforms to a residual video block associated with the current video block.

(165) After transform processing unit **208** generates a transform coefficient video block associated with the current video block, quantization unit **209** may quantize the transform coefficient video block associated with the current video block based on one or more quantization parameter (QP) values associated with the current video block.

(166) Inverse quantization unit **210** and inverse transform unit **211** may apply inverse quantization and inverse transforms to the transform coefficient video block, respectively, to reconstruct a residual video block from the transform coefficient video block. Reconstruction unit **212** may add the reconstructed residual video block to corresponding samples from one or more predicted video blocks generated by the prediction unit **202** to produce a reconstructed video block associated with the current block for storage in the buffer **213**.

(167) After reconstruction unit **212** reconstructs the video block, loop filtering operation may be performed reduce video blocking artifacts in the video block.

(168) Entropy encoding unit **214** may receive data from other functional components of the video encoder **200**. When entropy encoding unit **214** receives the data, entropy encoding unit **214** may perform one or more entropy encoding operations to generate entropy encoded data and output a bitstream that includes the entropy encoded data.

(169) FIG. **6** is a block diagram illustrating an example of video decoder **300** which may be video decoder **124** in the system **100** illustrated in FIG. **4**.

(170) The video decoder **300** may be configured to perform any or all of the embodiments of this disclosure. In the example of FIG. **6**, the video decoder **300** includes a plurality of functional components. The embodiments described in this disclosure may be shared among the various components of the video decoder **300**. In some examples, a processor may be configured to perform any or all of the embodiments described in this disclosure.

(171) In the example of FIG. **6**, video decoder **300** includes an entropy decoding unit **301**, a motion compensation unit **302**, an intra prediction unit **303**, an inverse quantization unit **304**, an inverse transformation unit **305**, a reconstruction unit **306**, and a buffer **307**. Video decoder **300** may, in some examples, perform a decoding pass generally reciprocal to the encoding pass described with respect to video encoder **200** (FIG. **5**).

(172) Entropy decoding unit **301** may retrieve an encoded bitstream. The encoded bitstream may include entropy coded video data (e.g., encoded blocks of video data). Entropy decoding unit **301** may decode the entropy coded video data, and from the entropy decoded video data, motion compensation unit **302** may determine motion information including motion vectors, motion vector precision, reference picture list indexes, and other motion information. Motion compensation unit **302** may, for example, determine such information by performing the AMVP and merge mode.

(173) Motion compensation unit **302** may produce motion compensated blocks, possibly performing interpolation based on interpolation filters. Identifiers for interpolation filters to be used with sub-pixel precision may be included in the syntax elements.

(174) Motion compensation unit **302** may use interpolation filters as used by video encoder **200** during encoding of the video block to calculate interpolated values for sub-integer pixels of a reference block. Motion compensation unit **302** may determine the interpolation filters used by video encoder **200** according to received syntax information and use the interpolation filters to produce predictive blocks.

(175) Motion compensation unit **302** may use some of the syntax information to determine sizes of blocks used to encode frame(s) and/or slice(s) of the encoded video sequence, partition information that describes how each macroblock of a picture of the encoded video sequence is partitioned, modes indicating how each partition is encoded, one or more reference frames (and reference frame lists) for each inter-encoded block, and other information to decode the encoded video sequence.

(176) Intra prediction unit **303** may use intra prediction modes for example received in the bitstream to form a prediction block from spatially adjacent blocks. Inverse quantization unit **304** inverse quantizes, i.e., de-quantizes, the quantized video block coefficients provided in the bitstream and decoded by entropy decoding unit **301**. Inverse transformation unit **305** applies an inverse transform.

(177) Reconstruction unit **306** may sum the residual blocks with the corresponding prediction blocks generated by motion compensation unit **302** or intra-prediction unit **303** to form decoded blocks. If desired, a deblocking filter may also be applied to filter the decoded blocks in order to remove blockiness artifacts. The decoded video blocks are then stored in buffer **307**, which provides reference blocks for subsequent motion compensation/intra prediction and also produces decoded video for presentation on a display device.

(178) A listing of solutions describe some embodiments of the present disclosure.

(179) A first set of solutions is provided next. The following solutions show example embodiments discussed in the previous section (e.g., item 1).

(180) 1. A video processing method (e.g., method **300** depicted in FIG. 3), comprising: performing (**302**) a conversion between a video having one or more pictures and a coded representation of the video, wherein each of the one or more pictures comprise exactly one slice, wherein the coded representation conforms to a format rule, wherein the format rule specifies that a first field in the coded representation indicative of a profile, a tier and a level that the coded representation conforms to, includes a second field indicative of whether a syntax structure that signals various constraints observed during the conversion is present in the first field.

(181) 2. The method of solution 1, wherein the syntax structure comprises a `general_constraint_info()` syntax structure.

(182) 3. The method of any of solutions 1-2, wherein the first field comprises profile, tier, level (PTL) syntax structure.

(183) 4. The method of any of solutions 1-3, wherein the second field is a single bit flag.

(184) The following solutions show example embodiments discussed in the previous section (e.g., item 2).

(185) 5. A method of video processing, comprising: performing a conversion between a video comprising one or more pictures and one or more slices and a coded representation of the video, wherein the coded representation conforms to a format rule, wherein the format rule specifies that values of one or more constraint flags at a first level in the coded representation control occurrence of one or more syntax elements at a sequence parameter set (SPS) level or a picture header (PH) level of a slice header (SH) level.

(186) 6. The method of solution 5, wherein the format rule specifies to include a syntax element at the SPS level if and only if `max_chroma_format_constraint_idc` is not equal to a specific value at the first level.

(187) 7. The method of solution 6, wherein the syntax element at SPS level comprises a chroma format IDC syntax element.

(188) 8. The method of solution 5, wherein the format rule specifies to include a syntax element at the PH level if and only if a general constraint flag is set for a specific value.

(189) 9. The method of solution 5, wherein the format rule specifies to include a syntax element at the SH level if and only if a general constraint flag is set for a specific value.

(190) The following solutions show example embodiments discussed in the previous section (e.g., item 3).

(191) 10. A method of video processing, comprising: performing a conversion between a video comprising one or more pictures and one or more slices and a coded representation of the video, wherein the coded representation conforms to a format rule, wherein the format rule specifies that values of one or more constraint flags at a first level in the coded representation constrain values of one or more syntax elements at picture parameter set (PPS) level.

(192) 11. The method of solution 10, wherein the one or more constraint flags at the first level include a flag indicating presence of a single tile per picture, and wherein the format rule specifies that fields

indicating number of tile rows and number of tile columns have a zero value at the PPS level.

(193) The following solutions show example embodiments discussed in the previous section (e.g., item 4).

(194) 12. The method of any of previous or subsequent solutions, wherein a first syntax portion in the first field controls values and/or occurrence of a second syntax portion in the first field.

(195) 13. The method of solution 12, wherein the second syntax portion occurs in the first field if and only if the first syntax portion indicates prespecified values.

(196) 14. The method of solution 13, wherein the first syntax portion comprises `one_slice_per_pic_constraint_flag` and wherein format rule specifies that `one_subpic_per_pic_constraint_flag` is omitted from the coded representation when `one_subpic_per_pic_constraint_flag` is equal to zero.

(197) The following solutions show example embodiments discussed in the previous section (e.g., item 7).

(198) 15. A method of video processing, comprising: performing a conversion between a video comprising one or more pictures and one or more slices and a coded representation of the video, wherein the coded representation conforms to a format rule that specifies that the coded representation includes an adaptation parameter set that includes syntax elements for identifiers of a video parameter set and/or a sequence parameter set and/or a picture parameter set.

(199) 16. The method of solution 15, wherein the format rule specifies that one or more constraint flags control values and/or occurrence of one or more syntax elements in the adaptation parameter set.

(200) 17. The method of solution 16, the one or more syntax elements in the adaptation parameter set include one or more of `alf_luma_filter_signal_flag`, `alf_chroma_filter_signal_flag`, `alf_cc_cb_filter_signal_flag` or `alf_cc_cr_filter_signal_flag`.

(201) 18. The method of solution 16, wherein the one or more constraint flags are included in a sequence parameter set or a picture parameter set that is identified by a corresponding identifier.

(202) The following solutions show example embodiments discussed in the previous section (e.g., item 8).

(203) 19. A method of video processing, comprising: performing a conversion between a video comprising one or more pictures and one or more slices and a coded representation of the video, wherein the coded representation conforms to a format rule that specifies to include one or more general constraint flags applicable to the conversion, wherein the one or more general constraint flags are indicative of applicability of general constraint info included in the coded representation to the conversion.

(204) 20. The method of solution 19, wherein the applicability of general constraint info is indicated for profiles, levels or tiers for which the general constraint info is applicable.

(205) 21. The method of solution 19, wherein the format rule specifies that the general constraint info is included in a sequence parameter set.

(206) 22. The method of solution 19, wherein the format rule specifies that the general constraint info is included in a video parameter set.

(207) The following solutions show example embodiments discussed in the previous section (e.g., item 9).

(208) 23. A method of video processing, comprising: performing a conversion between a video and a coded representation of the video, wherein the coded representation conforms to a format rule, wherein the format rule specifies that the coded representation conditionally includes a general constraint structure carrying general constraint information based on a characteristic of the video or the conversion.

(209) 24. The method of solution 23, wherein the characteristic of the video or the conversion comprises a profile or a level or a tier or a sub-profile used for the conversion.

(210) 25. The method of solutions 23-24, wherein the format rule specifies that the general constraint structure is included in a profile tier level syntax structure to which the general constraint information is applicable.

(211) 26. The method of any of solutions 23-25, wherein the general constraint information indicates a relationship between at least some coding tools and corresponding profiles or levels to which the coding tools are applicable.

(212) 27. The method of any of solutions 23-26, wherein the format rule specifies to omit the general constraint structure for a specific profile and/or a specific sub-profile and/or a specific level and/or a specific tier.

(213) 28. The method of any of solutions 23-27, wherein the format rule specifies to set an intra only constrain flag to 1 due to all-intra coding being used in a profile or a sub-profile.

- (214) 29. A video processing method, comprising: performing a conversion between a video and a coded representation of the video, wherein the coded representation conforms to a format rule, wherein the format rule specifies to include a first syntax element that indicates whether one or more second syntax elements are included in a profile, tier, level information field in the coded representation or a general constraints field in the coded representation.
- (215) 30. The method of solution 29, wherein the first syntax element signals that the one or more second syntax elements are not included in the coded representation.
- (216) 31. A video processing method, comprising: performing a conversion between a video and a coded representation of the video, wherein the coded representation conforms to a format rule, wherein the format rule specifies that a syntax field indicative of general constraints is selectively included in the coded representation depending on a profile or a level used for the conversion.
- (217) 32. The method of solution 31, wherein the format rule further specifies that allowed values of the syntax field are constrained by the profile or the level.
- (218) 33. The method of any of solutions 1 to 32, wherein the conversion comprises encoding the video into the coded representation.
- (219) 34. The method of any of solutions 1 to 32, wherein the conversion comprises decoding the coded representation to generate pixel values of the video.
- (220) 35. A video decoding apparatus comprising a processor configured to implement a method recited in one or more of solutions 1 to 34.
- (221) 36. A video encoding apparatus comprising a processor configured to implement a method recited in one or more of solutions 1 to 34.
- (222) 37. A computer program product having computer code stored thereon, the code, when executed by a processor, causes the processor to implement a method recited in any of solutions 1 to 34.
- (223) 38. A method, apparatus or system described in the present disclosure.
- (224) A second set of solutions show example embodiments discussed in the previous section (e.g., items 14a).
- (225) 1. A method of video processing (e.g., method **700** as shown in FIG. 7), comprising: performing **702** a conversion between a video and a bitstream of the video according to a rule, and wherein the rule specifies that a syntax element is included in a profile, tier, level information syntax structure to indicate whether one or more general constraint information syntax elements are included in a general constraint information syntax structure and/or whether the general constraint information syntax structure is included in the profile, tier, level information syntax structure.
- (226) 2. The method of solution 1, wherein whether the one or more general constraint information syntax elements are present or not are conditioned on a value of the syntax element.
- (227) 3. The method of solution 1, wherein the rule specifies that in responsive to the syntax element specifying that general constraint information is not present, the general constraint information syntax structure is not included in the profile, tier, level information syntax structure.
- (228) 4. The method of solution 3, wherein a value of the syntax element specifying that general constraint information is not present is equal to 0.
- (229) 5. The method of solution 1, wherein the rule specifies that each of the one or more general constraint information syntax elements is inferred to be a value such that a corresponding constraint is not imposed, in case that the general constraint information syntax structure is not present in the profile, tier, level syntax structure, or that the one or more general constraint information syntax elements are not present in the general constraint information syntax structure.
- (230) 6. The method of solution 5, wherein the value is 0.
- (231) 7. The method of solution 1, wherein the rule specifies to infer a value of a first general constraint information syntax element that specifies a requirement of bitstream conformance on a maximum bitdepth indication of samples to be equal to 8 in case that the syntax element has a particular value for the profile, tier, level information syntax structure that is present.
- (232) 8. The method of solution 7, wherein the rule specifies to infer a value of a second general constraint information syntax element that specifies a requirement of bitstream conformance on a maximum chroma format indication to be equal to 3 in case that the syntax element has a particular value for the profile, tier, level information syntax structure that is present.

- (233) 9. The method of solution 8, wherein the rule specifies to infer a value of some general constraint information syntax elements to be equal to 0 in case that the syntax element has a particular value for the profile, tier, level information syntax structure that is present.
- (234) 10. The method of solution 9, wherein the some general constraint information syntax elements are syntax elements included in the general constraint information syntax structure except the first general constraint information syntax element and the second general constraint information syntax element.
- (235) 11. The method of solution 10, wherein the some general constraint information syntax elements are included in the general constraint information syntax structure such that the some general constraint information syntax elements are from a third general constraint information syntax element specifying a presence of frame packing arrangement SEI messages, segmented rectangular frame packing arrangement SEI messages, equirectangular projection SEI messages, or cubemap projection SEI messages to a fourth general constraint information syntax element specifying a requirement of bitstream conformance on no network abstraction layer (NAL) unit of NAL unit type APS_NUT present in the bitstream.
- (236) 12. The method of solution 1, wherein the rule further specifies to infer a value of a general constraint information syntax element to be a default value, in case that the constraint information syntax element is not present.
- (237) 13. The method of solution 12, wherein the default value is 0 or 1.
- (238) 14. The method of solution 12, wherein the default value depends on profiles and/or levels.
- (239) 15. The method of solution 1, wherein the rule further specifies that signalling of the syntax element is conditioned on profiles and/or levels.
- (240) 16. The method of solution 15, wherein the rule further specifies to infer a value of the syntax element to be a default value, in case that the syntax element is not present.
- (241) 17. The method of solution 15, wherein the default value is 0 or 1.
- (242) 18. The method of solution 1, wherein the syntax element is u(1) coded.
- (243) 19. The method of any of solutions 1 to 18, wherein the conversion includes encoding the video into the bitstream.
- (244) 20. The method of any of solutions 1 to 18, wherein the conversion includes decoding the video from the bitstream.
- (245) 21. The method of any of solutions 1 to 18, wherein the conversion includes generating the bitstream from the video, and the method further comprises: storing the bitstream in a non-transitory computer-readable recording medium.
- (246) 22. A video processing apparatus comprising a processor configured to implement a method recited in any one or more of solutions 1 to 21.
- (247) 23. A method of storing a bitstream of a video, comprising, a method recited in any one of solutions 1 to 21, and further including storing the bitstream to a non-transitory computer-readable recording medium.
- (248) 24. A computer readable medium storing program code that, when executed, causes a processor to implement a method recited in any one or more of solutions 1 to 21.
- (249) 25. A computer readable medium that stores a bitstream generated according to any of the above described methods.
- (250) 26. A video processing apparatus for storing a bitstream representation, wherein the video processing apparatus is configured to implement a method recited in any one or more of solutions 1 to 21.
- (251) A third set of solutions show example embodiments discussed in the previous section (e.g., items 14b and 14c).
- (252) 1. A method of video processing (e.g., method **800** as shown in FIG. **8A**), comprising: performing **802** a conversion between a video and a bitstream of the video according to a rule, wherein a syntax structure includes information of one or more video coding layers that are included in the bitstream and correspond to one or more output layer sets, and wherein the rule specifies that a starting position of a syntax element in the syntax structure that specifies a level information to which the one or more output layer sets conform is constrained to align to a byte boundary.
- (253) 2. The method of solution 1, wherein the syntax structure further specifies at least one of profile, tier, sub-profile, and general constraints information to which the one or more output layer sets conform.
- (254) 3. The method of solution 1, wherein the syntax structure is a profile, tier, level information syntax

structure.

(255) 4. The method of any of solutions 1-3, wherein the one or more output layer sets are specified by a video parameter set in case that the profile, tier, level information syntax structure is included in the video parameter set.

(256) 5. The method of solution 1, wherein the one or more output layer sets refer to an output layer set that includes only a layer that is a lowest layer among layers that refer to a sequence parameter set in case that a profile, tier, level information syntax structure is included in the sequence parameter set.

(257) 6. The method of any of solutions 1-5, wherein the rule specifies that the starting position of the syntax element is required to be at a byte boundary.

(258) 7. The method of any of solutions 1-5, wherein the rule specifies to add one or more alignment syntax elements to make the starting position of the syntax element to be aligned to the byte boundary.

(259) 8. The method of solution 7, wherein the one or more alignment syntax elements are signalled before the syntax element.

(260) 9. The method of solution 7, wherein each of the one or more alignment syntax elements is coded with a fixed pattern bit string using one bit.

(261) 10. A method of video processing (e.g., method **810** as shown in FIG. **8B**), comprising: performing **812** a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies that a syntax structure indicates constraint information about the bitstream, wherein the rule specifies that the syntax structure is allowed to include a syntax element without aligning to a byte boundary.

(262) 11. The method of solution 10, wherein the rule specifies that the syntax element is included in the syntax structure without being checked whether the syntax element is aligned to the byte boundary or not.

(263) 12. The method of solution 10 or 11, wherein the syntax structure comprises a constraint flag.

(264) 13. The method of any of solutions 1 to 12, wherein the conversion includes encoding the video into the bitstream.

(265) 14. The method of any of solutions 1 to 12, wherein the conversion includes decoding the video from the bitstream.

(266) 15. The method of any of solutions 1 to 12, wherein the conversion includes generating the bitstream from the video, and the method further comprises: storing the bitstream in a non-transitory computer-readable recording medium.

(267) 16. A video processing apparatus comprising a processor configured to implement a method recited in any one or more of solutions 1 to 15.

(268) 17. A method of storing a bitstream of a video, comprising, a method recited in any one of solutions 1 to 15, and further including storing the bitstream to a non-transitory computer-readable recording medium.

(269) 18. A computer readable medium storing program code that, when executed, causes a processor to implement a method recited in any one or more of solutions 1 to 15.

(270) 19. A computer readable medium that stores a coded representation or a bitstream representation generated according to any of the above described methods.

(271) 20. A video processing apparatus for storing a bitstream representation, wherein the video processing apparatus is configured to implement a method recited in any one or more of solutions 1 to 15.

(272) A fourth set of solutions show example embodiments discussed in the previous section (e.g., items 14d, 15 and 16).

(273) 1. A method of video processing (e.g., method **900** as shown in FIG. **9A**), comprising: performing **902** a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies where and how reserved bits are included in a syntax structure that indicates one or more coding constraints applicable to the conversion.

(274) 2. The method of solution 1, wherein the syntax structure is a general constraints information syntax structure.

(275) 3. The method of solution 1 or 2, wherein the rule further specifies to include a first syntax element indicative of a number of the reserved bits in the syntax structure.

(276) 4. The method of solution 3, wherein the first syntax element is coded with unsigned integer using N bits, wherein N is an integer.

- (277) 5. The method of solution 4, wherein N is 8 or 11.
- (278) 6. The method of solution 1, wherein the first syntax element of the reserved bit is coded with unsigned integer using 0-th order Exp-Golomb-code.
- (279) 7. The method of solution 3, wherein a reserved general constraints information syntax element is included in the syntax structure.
- (280) 8. The method of solution 7, wherein the reserved general constraints information syntax element is `gci_reserved_zero_bit[i]`, wherein i ranges from 0 to a value of the first syntax element minus 1.
- (281) 9. The method of solution 1, wherein a first reserved bit and a last reserved bit are at a byte boundary.
- (282) 10. A method of video processing (e.g., method **910** as shown in FIG. **9B**), comprising: determining **912**, for a conversion between a video comprising one or more pictures comprising one or more slices and a bitstream of the video, that only I slices are enabled for the conversion according to a rule; and performing **914** the conversion according to the determining, wherein the rule specifies that, responsive to only I slices being enabled, the bitstream conforms to one or more additional constraints.
- (283) 11. The method of solution 10, wherein the one or more additional constraints constrain syntax elements related to a reference picture list to a certain value that specifies not to use the reference picture list.
- (284) 12. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to a long-term reference picture to a certain value that specifies not to allow the long-term reference picture.
- (285) 13. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to a reference picture list to a certain value that specifies not to allow the reference picture list for an instantaneous decoding refresh (IDR) picture.
- (286) 14. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to a number of reference picture lists to a certain value that specifies the number of reference picture lists is 0.
- (287) 15. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to use of an inter-layer prediction to a certain value that specifies all layers are coded independently.
- (288) 16. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to an applicability of reference picture resampling to a certain value that specifies to disable the reference picture resampling.
- (289) 17. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to an applicability of resolution change to a certain value that specifies to disable the resolution change.
- (290) 18. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to an applicability of a weighted prediction for P slices and/or B slices to a certain value that specifies to disable the weighted prediction for P slices and/or B slices.
- (291) 19. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to an applicability of a sub-block transform to a certain value that specifies to disable the sub-block transform.
- (292) 20. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to an applicability of a gradual decoding refresh to a certain value that specifies to disable the gradual decoding refresh.
- (293) 21. The method of solution 10, wherein the one or more additional constraints constrain a syntax element related to an applicability of a coding tool for an inter picture to a certain value that specifies to disable the coding tool.
- (294) 22. The method of solution 21, wherein the coding tool includes a reference wraparound, temporal motion vector prediction, subblock-based temporal motion vector prediction, adaptive motion vector resolution, bi-directional optical flow, decoder-side motion vector refinement, affine, merge with motion vector difference, symmetric motion vector difference, prediction refinement with optical flow, bi-prediction with coding unit-level weights, combined inter-intra prediction, or geometric partitioning mode.
- (295) 23. The method of solution 10, wherein the constraint that allows only the I slice type is indicated by

a syntax element that specifies whether to impose the constraint.

(296) 24. The method of solution 23, wherein the syntax element further specifies that, for each coded slice network abstraction layer (NAL) unit, a NAL unit header (NUH) layer type is IDR_N_LP.

(297) 25. A method of video processing (e.g., method **920** as shown in FIG. **9C**), comprising: performing **922** a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies that one or more syntax elements in a sequence parameter set, a picture parameter set, a picture header, or a sequence header are constrained according to a general constraint information syntax element that indicates a constraint applicable to the conversion.

(298) 26. The method of solution 25, wherein the general constraint information syntax element specifies whether each picture contains only a single tile or not.

(299) 27. The method of solution 26, wherein the rule specifies, responsive to the general constraint information syntax element specifying that each picture contains only a single tile, to constrain a syntax element indicative of a number of tile columns to specify that the number of tile columns is required to be 1.

(300) 28. The method of solution 26, wherein the rule specifies, responsive to the general constraint information syntax element specifying that each picture contains only a single tile, to constrain a syntax element indicative of a number of tile rows to specify that the number of tile rows is required to be 1.

(301) 29. The method of solution 26, wherein the rule specifies, responsive to the general constraint information syntax element specifying that each picture contains only a single tile, to constrain a syntax element indicative of a slice partition mode to specify that a rectangular slice mode is in use for each picture referring to a picture parameter set.

(302) 30. The method of solution 25, wherein the general constraint information syntax element specifies whether no network abstraction layer (NAL) unit with NAL unit type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT is present.

(303) 31. The method of solution 30, wherein the general constraint information element constrains a syntax element indicative of an applicability of cross-component adaptive loop filtering to the conversion.

(304) 32. The method of solution 31, wherein the rule specifies, responsive to the general constraint information syntax element specifying no NAL unit with NAL unit type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT is present, to constrain the syntax element such that the cross-component adaptive loop filtering is disabled.

(305) 33. The method of solution 31, wherein the rule specifies, responsive to the general constraint information syntax element, no_aps_constraint_flag, equal to 1, to constrain a value of the syntax element, sps_ccalf_enabled_flag is to be equal to 0.

(306) 34. The method of solution 30, wherein the general constraint information element constrains the one or more syntax elements indicative of a number of adaptive loop filtering (ALF) luma adaptive parameter sets (APS).

(307) 35. The method of solution 34, wherein the rule specifies, responsive to the general constraint information syntax element specifying no NAL unit with NAL unit type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT is present, to constrain the one or more syntax elements such that the number of ALF APS s that slices in a current picture refer to is 0.

(308) 36. The method of solution 34, wherein the rule specifies, responsive to the general constraint information syntax element, no_aps_constraint_flag, equal to 1, to constrain a value of the one or more syntax elements, ph_num_alf_aps_ids_luma and slice_num_alf_aps_ids_luma is equal to 0.

(309) 37. The method of solution 30, wherein the general constraint information element constrains the one or more syntax elements indicative of an applicability of chroma adaptive loop filtering.

(310) 38. The method of solution 37, wherein the rule specifies, responsive to the general constraint information syntax element specifying no NAL unit with NAL unit type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT is present, to constrain the one or more syntax elements such that the chroma adaptive loop filtering is disabled and not applied to Cb and Cr color components for a current picture.

(311) 39. The method of solution 37, wherein the rule specifies, responsive to the general constraint information syntax element, no_aps_constraint_flag, equal to 1, to constrain a value of the one or more syntax elements, ph_alf_cb_flag, ph_alf_cr_flag, sh_alf_cb_flag, and sh_alf_cr_flag, to be equal to 0.

(312) 40. The method of solution 25, wherein the rule specifies, responsive to the general constraint

information syntax element specifying that each picture contains only a single slice, to constrain a syntax element indicative of a slice partition mode to specify that a rectangular slice mode is in use for each picture referring to a picture parameter set.

(313) 41. The method of solution 25, wherein the rule specifies, responsive to the general constraint information syntax element specifying that each picture contains only a single tile and that each picture contains only a single slice, to constrain a syntax element indicative of a picture partition mode to specify that there is no picture partition.

(314) 42. The method of solution 25, wherein the rule specifies, responsive to the general constraint information syntax element specifying that each picture contains only a single slice and that the single slice is a rectangular slice, to constrain a syntax element indicative of a number of slices in a picture to specify that the number of slices in the picture is equal to 1.

(315) 43. The method of solution 25, wherein the rule specifies, responsive to the general constraint information syntax element specifying that each picture contains only a single subpicture, to constrain a syntax element indicative of a number of subpictures in a picture to specify that the number of subpictures in the picture is equal to 1.

(316) 44. A method of video processing (e.g., method **930** as shown in FIG. **9D**), comprising: performing **932** a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies that whether or how a first syntax element in a syntax structure that indicates one or more constraints applicable to the conversion is indicated is dependent on whether or how a second syntax element is indicated in the syntax structure.

(317) 45. The method of solution 44, wherein the rule specifies that responsive to the second syntax element indicating that all the layers are coded independently, the first syntax element indicative of use of an inter-layer prediction in decoding of pictures that refer to a sequence parameter set is constrained to be equal to a value specifying no use of the inter-layer prediction.

(318) 46. The method of solution 44, wherein the rule specifies that responsive to the second syntax element indicating that no transform skip is available, the first syntax element indicative of enablement of block differential pulse coded modulation is constrained to be equal to a value specifying disablement of the block differential pulse coded modulation.

(319) 47. The method of solution 44, wherein the rule specifies that responsive to the second syntax element indicating no constraint on use of a luma mapping with chroma scaling, an explicit scaling list, or a cross component adaptive loop filtering, the first syntax element is constraint to be equal to a value specifying no constraint on non-presence of network abstraction unit (NAL) of NAL unit type equal to APS_NUT.

(320) 48. A method of video processing (e.g., method **940** as shown in FIG. **9E**), comprising: performing **942** a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies whether or how a syntax element indicative of general constraints on the conversion is included in the bitstream depends on a profile and/or a level used for the conversion.

(321) 49. The method of solution 48, wherein the rule specifies that a value of the syntax element is constrained by the profile and/or the level.

(322) 50. The method of solution 48, wherein the rule specifies that the syntax element is omitted responsive to the profile and/or the level not satisfying the rule.

(323) 51. The method of solution 48, wherein the rule specifies that the syntax element, when not present, is inferred to be a particular value.

(324) 52. The method of solution 51, wherein the particular value is 0 or 1.

(325) 53. The method of solution 51, wherein the particular value is dependent on the profile and/or the level.

(326) 54. The method of any of solutions 1 to 53, wherein the conversion includes encoding the video into the bitstream.

(327) 55. The method of any of solutions 1 to 53, wherein the conversion includes decoding the video from the bitstream.

(328) 56. The method of solutions 1 to 53, wherein the conversion includes generating the bitstream from the video, and the method further comprises: storing the bitstream in a non-transitory computer-readable recording medium.

(329) 57. A video processing apparatus comprising a processor configured to implement a method recited in any one or more of solutions 1 to 56.

(330) 58. A method of storing a bitstream of a video, comprising, a method recited in any one of solutions 1 to 56, and further including storing the bitstream to a non-transitory computer-readable recording medium.

(331) 59. A computer readable medium storing program code that, when executed, causes a processor to implement a method recited in any one or more of solutions 1 to 56.

(332) 60. A computer readable medium that stores a coded representation or a bitstream representation generated according to any of the above described methods.

(333) 61. A video processing apparatus for storing a bitstream representation, wherein the video processing apparatus is configured to implement a method recited in any one or more of solutions 1 to 56.

(334) In the present disclosure, the term “video processing” may refer to video encoding, video decoding, video compression or video decompression. For example, video compression algorithms may be applied during conversion from pixel representation of a video to a corresponding bitstream representation or vice versa. The bitstream representation of a current video block may, for example, correspond to bits that are either co-located or spread in different places within the bitstream, as is defined by the syntax. For example, a macroblock may be encoded in terms of transformed and coded error residual values and also using bits in headers and other fields in the bitstream. Furthermore, during conversion, a decoder may parse a bitstream with the knowledge that some fields may be present, or absent, based on the determination, as is described in the above solutions. Similarly, an encoder may determine that certain syntax fields are or are not to be included and generate the coded representation accordingly by including or excluding the syntax fields from the coded representation.

(335) The disclosed and other solutions, examples, embodiments, modules and the functional operations described in this disclosure can be implemented in digital electronic circuitry, or in computer software, firmware, or hardware, including the structures disclosed in this disclosure and their structural equivalents, or in combinations of one or more of them. The disclosed and other embodiments can be implemented as one or more computer program products, i.e., one or more modules of computer program instructions encoded on a computer readable medium for execution by, or to control the operation of, data processing apparatus. The computer readable medium can be a machine-readable storage device, a machine-readable storage substrate, a memory device, a composition of matter effecting a machine-readable propagated signal, or a combination of one or more them. The term “data processing apparatus” encompasses all apparatus, devices, and machines for processing data, including by way of example a programmable processor, a computer, or multiple processors or computers. The apparatus can include, in addition to hardware, code that creates an execution environment for the computer program in question, e.g., code that constitutes processor firmware, a protocol stack, a database management system, an operating system, or a combination of one or more of them. A propagated signal is an artificially generated signal, e.g., a machine-generated electrical, optical, or electromagnetic signal, that is generated to encode information for transmission to suitable receiver apparatus.

(336) A computer program (also known as a program, software, software application, script, or code) can be written in any form of programming language, including compiled or interpreted languages, and it can be deployed in any form, including as a stand-alone program or as a module, component, subroutine, or other unit suitable for use in a computing environment. A computer program does not necessarily correspond to a file in a file system. A program can be stored in a portion of a file that holds other programs or data (e.g., one or more scripts stored in a markup language document), in a single file dedicated to the program in question, or in multiple coordinated files (e.g., files that store one or more modules, sub programs, or portions of code). A computer program can be deployed to be executed on one computer or on multiple computers that are located at one site or distributed across multiple sites and interconnected by a communication network.

(337) The processes and logic flows described in this disclosure can be performed by one or more programmable processors executing one or more computer programs to perform functions by operating on input data and generating output. The processes and logic flows can also be performed by, and apparatus can also be implemented as, special purpose logic circuitry, e.g., a field-programmable gate array (FPGA) or an application-specific integrated circuit (ASIC).

(338) Processors suitable for the execution of a computer program include, by way of example, both general and special purpose microprocessors, and any one or more processors of any kind of digital computer. Generally, a processor will receive instructions and data from a read only memory or a random-access memory or both. The essential elements of a computer are a processor for performing instructions and one or more memory devices for storing instructions and data. Generally, a computer will also include, or be operatively coupled to receive data from or transfer data to, or both, one or more mass storage devices for storing data, e.g., magnetic, magneto optical disks, or optical disks. However, a computer need not have such devices. Computer readable media suitable for storing computer program instructions and data include all forms of non-volatile memory, media and memory devices, including by way of example semiconductor memory devices, e.g., erasable programmable read-only memory (EPROM), electronically erasable programmable read-only memory (EEPROM), and flash memory devices; magnetic disks, e.g., internal hard disks or removable disks; magneto optical disks; and compact disc, read-only memory (CD-ROM) and digital versatile disc, read-only memory (DVD-ROM) disks. The processor and the memory can be supplemented by, or incorporated in, special purpose logic circuitry.

(339) While the present disclosure contains many specifics, these should not be construed as limitations on the scope of any subject matter or of what may be claimed, but rather as descriptions of features that may be specific to particular embodiments of the present disclosure. Certain features that are described in the present disclosure in the context of separate embodiments can also be implemented in combination in a single embodiment. Conversely, various features that are described in the context of a single embodiment can also be implemented in multiple embodiments separately or in any suitable subcombination. Moreover, although features may be described above as acting in certain combinations and even initially claimed as such, one or more features from a claimed combination can in some cases be excised from the combination, and the claimed combination may be directed to a subcombination or variation of a subcombination.

(340) Similarly, while operations are depicted in the drawings in a particular order, this should not be understood as requiring that such operations be performed in the particular order shown or in sequential order, or that all illustrated operations be performed, to achieve desirable results. Moreover, the separation of various system components in the embodiments described in the present disclosure should not be understood as requiring such separation in all embodiments.

(341) Only a few implementations and examples are described and other implementations, enhancements and variations can be made based on what is described and illustrated in the present disclosure.

Claims

1. A method of video processing, comprising: performing a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies a first syntax element indicating a number of reserved bits in a general constraint information syntax structure is included in a general constraint information syntax structure.
2. The method of claim 1, wherein the first syntax element is coded with unsigned integer using M bits, wherein M is an integer.
3. The method of claim 1, wherein a reserved general constraints information syntax element is included in the general constraint information syntax structure, and wherein the reserved general constraints information syntax element is `gci_reserved_zero_bit[i]`, wherein i ranges from 0 to a value of the first syntax element minus 1.
4. The method of claim 3, wherein the reserved general constraints information syntax element is coded with unsigned integer using S bits, wherein S is equal to 1.
5. The method of claim 1, wherein the rule specifies that a second syntax element is included in a profile, tier, level information syntax structure when a value of a profile tier present flag is equal to one, which indicates that profile, tier, and general constraints information is allowed to be present, wherein a value of the second syntax element indicates whether one or more general constraint information syntax elements are included in the general constraint information syntax structure, and wherein when the value of the second syntax element is equal to zero, the one or more general constraint information syntax elements are not included in the general constraint information syntax structure, and the general constraint information

syntax structure does not impose any constraint.

6. The method of claim 5, wherein the second syntax element is coded with unsigned integer using N bits, wherein N is equal to 1.

7. The method of claim 1, wherein a third syntax element specifying a level information to which one or more output layer sets conform is included in a profile, tier, level information syntax structure, and wherein the rule specifies that a starting position of the third syntax element in the profile, tier, level information syntax structure is constrained to align to a byte boundary.

8. The method of claim 1, wherein the rule specifies that one or more syntax elements in a sequence parameter set, a picture parameter set, a picture header, or a slice header are constrained according to a fourth syntax element included in the general constraint information syntax structure, and wherein the fourth syntax element specifies whether no network abstraction layer (NAL) unit with NAL unit type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT is present, and wherein when a value of the fourth syntax element is equal to 1 and specifies that no NAL unit with NAL unit type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT is present: a value of a fifth syntax element in the sequence parameter set is constrained to be equal to 0, which specifies that a cross-component adaptive loop filter is disabled; a value of a sixth syntax element in the picture header is constrained to be equal to 0, which specifies that a number of adaptive loop filter (ALF) adaptive parameter sets (APSs) that a picture refers to is equal to 0; a value of a seventh syntax element in the slice header is constrained to be equal to 0, which specifies that a number of ALF APS that a slice refers to is equal to 0; a value of an eighth syntax element in the picture header is constrained to be equal to 0, which specifies that the adaptive loop filter is disabled for a Cb color component of a picture; a value of a ninth syntax element in the picture header is constrained to be equal to 0, which specifies that the adaptive loop filter is disabled for a Cr color component of a picture; a value of a tenth syntax element in the slice header is constrained to be equal to 0, which specifies that the adaptive loop filter is disabled for a Cb color component of a slice; and a value of an eleventh syntax element in the slice header is constrained to be equal to 0, which specifies that the adaptive loop filter is disabled for a Cr color component of a slice.

9. The method of claim 1, wherein the conversion includes encoding the video into the bitstream.

10. The method of claim 1, wherein the conversion includes decoding the video from the bitstream.

11. An apparatus for processing video data comprising a processor and a non-transitory memory with instructions thereon, wherein the instructions upon execution by the processor, cause the processor to: perform a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies a first syntax element indicating a number of reserved bits in a general constraint information syntax structure is included in a general constraint information syntax structure.

12. The apparatus of claim 11, wherein the first syntax element is coded with unsigned integer using M bits, wherein M is an integer, wherein a reserved general constraints information syntax element is included in the general constraint information syntax structure, wherein the reserved general constraints information syntax element is `gci_reserved_zero_bit[i]`, wherein i ranges from 0 to a value of the first syntax element minus 1, and wherein the reserved general constraints information syntax element is coded with unsigned integer using S bits, wherein S is equal to 1.

13. The apparatus of claim 11, wherein the rule specifies that a second syntax element is included in a profile, tier, level information syntax structure when a value of a profile tier present flag is equal to one, which indicates that profile, tier, and general constraints information is allowed to be present, wherein a value of the second syntax element indicates whether one or more general constraint information syntax elements are included in the general constraint information syntax structure, and wherein when the value of the second syntax element is equal to zero, the one or more general constraint information syntax elements are not included in the general constraint information syntax structure, and the general constraint information syntax structure does not impose any constraint.

14. The apparatus of claim 13, wherein the second syntax element is coded with unsigned integer using N bits, wherein N is equal to 1.

15. The apparatus of claim 11, wherein a third syntax element specifying a level information to which one or more output layer sets conform is included in a profile, tier, level information syntax structure, and wherein the rule specifies that a starting position of the third syntax element in the profile, tier, level information syntax structure is constrained to align to a byte boundary.

16. The apparatus of claim 11, wherein the rule specifies that one or more syntax elements in a sequence parameter set, a picture parameter set, a picture header, or a slice header are constrained according to a fourth syntax element included in the general constraint information syntax structure, and wherein the fourth syntax element specifies whether no network abstraction layer (NAL) unit with NAL unit type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT is present, and wherein when a value of the fourth syntax element is equal to 1 and specifies that no NAL unit with NAL unit type equal to PREFIX_APS_NUT or SUFFIX_APS_NUT is present: a value of a fifth syntax element in the sequence parameter set is constrained to be equal to 0, which specifies that a cross-component adaptive loop filter is disabled; a value of a sixth syntax element in the picture header is constrained to be equal to 0, which specifies that a number of adaptive loop filter (ALF) adaptive parameter sets (APSs) that a picture refers to is equal to 0; a value of a seventh syntax element in the slice header is constrained to be equal to 0, which specifies that a number of ALF APS that a slice refers to is equal to 0; a value of an eighth syntax element in the picture header is constrained to be equal to 0, which specifies that the adaptive loop filter is disabled for a Cb color component of a picture; a value of a ninth syntax element in the picture header is constrained to be equal to 0, which specifies that the adaptive loop filter is disabled for a Cr color component of a picture; a value of a tenth syntax element in the slice header is constrained to be equal to 0, which specifies that the adaptive loop filter is disabled for a Cb color component of a slice; and a value of an eleventh syntax element in the slice header is constrained to be equal to 0, which specifies that the adaptive loop filter is disabled for a Cr color component of a slice.

17. A non-transitory computer-readable storage medium storing instructions that cause a processor to: perform a conversion between a video and a bitstream of the video according to a rule, wherein the rule specifies a first syntax element indicating a number of reserved bits in a general constraint information syntax structure is included in a general constraint information syntax structure.

18. The non-transitory computer-readable storage medium of claim 17, wherein the first syntax element is coded with unsigned integer using M bits, wherein M is an integer, wherein a reserved general constraints information syntax element is included in the general constraint information syntax structure, wherein the reserved general constraints information syntax element is `gci_reserved_zero_bit[i]`, wherein i ranges from 0 to a value of the first syntax element minus 1, and wherein the reserved general constraints information syntax element is coded with unsigned integer using S bits, wherein S is equal to 1.

19. A non-transitory computer-readable recording medium storing a bitstream of a video which is generated by a method performed by a video processing apparatus, wherein the method comprises: generating the bitstream of the video according to a rule, wherein the rule specifies a first syntax element indicating a number of reserved bits in a general constraint information syntax structure is included in a general constraint information syntax structure.

20. The non-transitory computer-readable recording medium of claim 19, wherein the first syntax element is coded with unsigned integer using M bits, wherein M is an integer, wherein a reserved general constraints information syntax element is included in the general constraint information syntax structure, wherein the reserved general constraints information syntax element is `gci_reserved_zero_bit[i]`, wherein i ranges from 0 to a value of the first syntax element minus 1, and wherein the reserved general constraints information syntax element is coded with unsigned integer using S bits, wherein S is equal to 1.
