

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12400779
Kind Code	B1
Date of Patent	August 26, 2025
Inventor(s)	Partovi; Afshin

Magnetic structure for inductive charging

Abstract

A magnetic structure for inductive charging is provided. In accordance with an embodiment, the magnetic structure generates a magnetic field that creates a magnetic attachment between an inductive charger and an electronic device and aligns an inductive charger coil with a receiver coil for inductive power transfer. The magnetic structure includes two or more discontinuous arc-shaped permanent magnet sections. The magnetic structure is configured such that the magnetic field generated by the magnetic structure does not impair operation of a magnetic shield layer during inductive power transfer, and the electronic device can be rotated across a continuous range of rotational angles with respect to the inductive charger while keeping the alignment between the inductive charger coil and the inductive receiver coil during inductive power transfer.

Inventors:	Partovi; Afshin (Palo Alto, CA)
Applicant:	Mojo Mobility Inc. (Palo Alto, CA)
Family ID:	1000008591155
Assignee:	Mojo Mobility Inc. (Palo Alto, CA)
Appl. No.:	19/197324
Filed:	May 02, 2025

Related U.S. Application Data

continuation parent-doc US 17522367 20211109 US 12293872 child-doc US 19197324
continuation parent-doc US 17492083 20211001 US 12278045 20250415 child-doc US 17522367
continuation parent-doc US 16538452 20190812 US 11283306 20220322 child-doc US 17492083
continuation parent-doc US 14556760 20141201 US 10714986 20200714 child-doc US 16538452
continuation parent-doc US 13708838 20121207 US 8901881 20141202 child-doc US 14556760
continuation parent-doc US 13158134 20110610 US 8890470 20141118 child-doc US 13708838
us-provisional-application US 61478015 20110421

Publication Classification

Int. Cl.: H02J50/90 (20160101); H01F7/02 (20060101); H02J7/00 (20060101); H02J50/12 (20160101); H02J50/40 (20160101); H02J50/70 (20160101); H02J50/80 (20160101); H02J50/00 (20160101)

U.S. Cl.:

CPC H01F7/0252 (20130101); H02J7/00034 (20200101); H02J7/0044 (20130101); H02J50/12 (20160201); H02J50/402 (20200101); H02J50/70 (20160201); H02J50/80 (20160201); H02J50/90 (20160201); H01F7/0247 (20130101); H02J50/005 (20200101)

Field of Classification Search

CPC: H02J (50/90)

USPC: 320/108

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
3938018	12/1975	Dahl	N/A	N/A
4311853	12/1981	Cree	N/A	N/A
4311953	12/1981	Fukuda	N/A	N/A
4415959	12/1982	Vinciarelli	N/A	N/A
4720667	12/1987	Lee et al.	N/A	N/A
4731585	12/1987	Fox	N/A	N/A
4800328	12/1988	Bolger	N/A	N/A
4829277	12/1988	Stahura et al.	N/A	N/A
4873677	12/1988	Sakamoto et al.	N/A	N/A
5237257	12/1992	Johnson	N/A	N/A
5311973	12/1993	Tseng	N/A	N/A
5367242	12/1993	Hulman	N/A	N/A
5434493	12/1994	Woody	N/A	N/A
5455466	12/1994	Parks et al.	N/A	N/A
5543702	12/1995	Pfeiffer	N/A	N/A
5550452	12/1995	Shirai	N/A	N/A
5583474	12/1995	Mizoguchi	N/A	N/A
5600225	12/1996	Goto	N/A	N/A
5642087	12/1996	Crow	N/A	N/A
5656917	12/1996	Theobald	N/A	N/A
5690693	12/1996	Wang	N/A	N/A
5696433	12/1996	Palino	N/A	N/A
5702431	12/1996	Wang	N/A	N/A
5733313	12/1997	Barreras, Sr.	N/A	N/A

5734254	12/1997	Stephens	N/A	N/A
5744933	12/1997	Inoue	N/A	N/A
5803744	12/1997	Yen	N/A	N/A
5808587	12/1997	Shima	N/A	N/A
5889384	12/1998	Hayes	N/A	N/A
5925814	12/1998	Tsuzuki	N/A	N/A
5952814	12/1998	Van Lerberghe	N/A	N/A
5959433	12/1998	Rohde	N/A	N/A
5963012	12/1998	Garcia	N/A	N/A
5991170	12/1998	Nagai	N/A	N/A
5991665	12/1998	Wang	N/A	N/A
6008622	12/1998	Nakawatase	N/A	N/A
6016046	12/1999	Kaile et al.	N/A	N/A
6028413	12/1999	Brockmann	N/A	N/A
6040680	12/1999	Toya et al.	N/A	N/A
6057668	12/1999	Chao	N/A	N/A
6094119	12/1999	Reznik	N/A	N/A
6118249	12/1999	Brockman et al.	N/A	N/A
6184651	12/2000	Fernandez et al.	N/A	N/A
6184654	12/2000	Bachner	N/A	N/A
6208115	12/2000	Binder	N/A	N/A
6301128	12/2000	Jang et al.	N/A	N/A
6310465	12/2000	Najima	N/A	N/A
6331744	12/2000	Chen	N/A	N/A
6366817	12/2001	Kung	N/A	N/A
6436299	12/2001	Baerman	N/A	N/A
6462509	12/2001	Abe	N/A	N/A
6489745	12/2001	Koreis	N/A	N/A
6498455	12/2001	Zink	N/A	N/A
6501364	12/2001	Hui	N/A	N/A
6527971	12/2002	Nakamura et al.	N/A	N/A
6573817	12/2002	Gottschalk	N/A	N/A
6586909	12/2002	Trepka	N/A	N/A
6625477	12/2002	Wakefield	N/A	N/A
6636017	12/2002	Zink et al.	N/A	N/A
6650088	12/2002	Webb	N/A	N/A
6673250	12/2003	Kuennen	N/A	N/A
6697272	12/2003	Nanbu	N/A	N/A
6731071	12/2003	Baerman	N/A	N/A
6741064	12/2003	Liu	N/A	N/A
6756656	12/2003	Lowther	N/A	N/A
6756765	12/2003	Bruning	N/A	N/A
6765144	12/2003	Wang et al.	N/A	N/A
6798716	12/2003	Charych	N/A	N/A
6803744	12/2003	Sabo	N/A	N/A
6803774	12/2003	Park	N/A	N/A
6806649	12/2003	Mollema	N/A	N/A
6812645	12/2003	Baerman	N/A	N/A
6825620	12/2003	Kuennen	N/A	N/A
6831417	12/2003	Baerman	N/A	N/A

6831544	12/2003	Patel et al.	N/A	N/A
6844702	12/2004	Giannopoulos	N/A	N/A
6869019	12/2004	Nagi et al.	N/A	N/A
6870089	12/2004	Gray	N/A	N/A
6888438	12/2004	Hui	N/A	N/A
6906495	12/2004	Cheng	N/A	N/A
6912137	12/2004	Berghegger	N/A	N/A
6913477	12/2004	Dayan	N/A	N/A
6917163	12/2004	Baarman	N/A	N/A
6917182	12/2004	Burton	N/A	N/A
6943733	12/2004	Vance	N/A	N/A
6960968	12/2004	Odendaal	N/A	N/A
6972543	12/2004	Wells	N/A	N/A
6975198	12/2004	Baarman	N/A	N/A
7026789	12/2005	Bozzone	N/A	N/A
7031662	12/2005	Suzuki	N/A	N/A
7042196	12/2005	Ka-Lai	N/A	N/A
7109682	12/2005	Takagi	N/A	N/A
7116200	12/2005	Baarman	N/A	N/A
7118240	12/2005	Baarman	N/A	N/A
7126450	12/2005	Baarman	N/A	N/A
7132918	12/2005	Baarman	N/A	N/A
7151357	12/2005	Xian	N/A	N/A
7162264	12/2006	Vance	N/A	N/A
7164245	12/2006	Chen	N/A	N/A
7164255	12/2006	Hui	N/A	N/A
7183870	12/2006	Takagi	N/A	N/A
7184706	12/2006	Someya	N/A	N/A
7209084	12/2006	Lindell	N/A	N/A
7211986	12/2006	Flowerdew et al.	N/A	N/A
7221919	12/2006	Takagi	N/A	N/A
7226442	12/2006	Sheppard, Jr.	N/A	N/A
7239110	12/2006	Cheng	N/A	N/A
7248017	12/2006	Cheng et al.	N/A	N/A
7305258	12/2006	Rydgren	N/A	N/A
7311526	12/2006	Rohrbach	N/A	N/A
7324051	12/2007	Hayes	N/A	N/A
7331793	12/2007	Hernandez et al.	N/A	N/A
7336054	12/2007	Crisp	N/A	N/A
7342539	12/2007	Rosenberg	N/A	N/A
7352567	12/2007	Hotelling et al.	N/A	N/A
7355150	12/2007	Baarman	N/A	N/A
7375493	12/2007	Calhoon et al.	N/A	N/A
7376408	12/2007	Hayes	N/A	N/A
7378817	12/2007	Calhoon	N/A	N/A
7382636	12/2007	Baarman	N/A	N/A
7385357	12/2007	Kuennen	N/A	N/A
7388543	12/2007	Vance	N/A	N/A
7399202	12/2007	Dayan	N/A	N/A
7415248	12/2007	Andersson et al.	N/A	N/A

7443135	12/2007	Cho	N/A	N/A
7462951	12/2007	Baerman	N/A	N/A
7477195	12/2008	Vance	N/A	N/A
7487921	12/2008	Takahashi	N/A	N/A
7495414	12/2008	Hui	N/A	N/A
7498871	12/2008	Ruuswik	N/A	N/A
7514765	12/2008	Huang et al.	N/A	N/A
7525283	12/2008	Cheng	N/A	N/A
7554316	12/2008	Stevens	N/A	N/A
7576514	12/2008	Hui	N/A	N/A
7605496	12/2008	Stevens	N/A	N/A
D603603	12/2008	Laine	N/A	N/A
D607879	12/2009	Ferber	N/A	N/A
7645143	12/2009	Rohrbach	N/A	N/A
D611407	12/2009	Webb	N/A	N/A
D611408	12/2009	Ferber	N/A	N/A
7733215	12/2009	Kozuma et al.	N/A	N/A
7741734	12/2009	Joannopoulos	N/A	N/A
7781916	12/2009	Boys	N/A	N/A
7782169	12/2009	Guenther	N/A	N/A
D624316	12/2009	Ferber	N/A	N/A
7791311	12/2009	Sagoo	N/A	N/A
7804054	12/2009	Shalom	N/A	N/A
D625721	12/2009	Ferber	N/A	N/A
7825543	12/2009	Karalis	N/A	N/A
7855529	12/2009	Liu	N/A	N/A
7872445	12/2010	Hui	N/A	N/A
7906936	12/2010	Azancot	N/A	N/A
7915858	12/2010	Liu	N/A	N/A
D636333	12/2010	Kulikowski	N/A	N/A
7948208	12/2010	Partovi	N/A	N/A
7952322	12/2010	Partovi	N/A	N/A
D639734	12/2010	Ferber	N/A	N/A
8004235	12/2010	Baerman	N/A	N/A
8005547	12/2010	Forsberg	N/A	N/A
8013568	12/2010	Park	N/A	N/A
8035255	12/2010	Kurs	N/A	N/A
8040103	12/2010	Hui	N/A	N/A
8049370	12/2010	Azancot	N/A	N/A
8050068	12/2010	Hussmann	N/A	N/A
8069100	12/2010	Taylor et al.	N/A	N/A
8090550	12/2011	Azancot	N/A	N/A
8115448	12/2011	John	N/A	N/A
8133764	12/2011	Dirks	N/A	N/A
8169185	12/2011	Partovi	N/A	N/A
8212518	12/2011	Pijnenburg	N/A	N/A
8222860	12/2011	Kamijo	N/A	N/A
8234189	12/2011	Taylor et al.	N/A	N/A
8234509	12/2011	Gioscia et al.	N/A	N/A
8242741	12/2011	Phelps, III	N/A	N/A

8243049	12/2011	Vos	N/A	N/A
8290463	12/2011	Liu et al.	N/A	N/A
8369905	12/2012	Sogabe	N/A	N/A
8390249	12/2012	Walley	N/A	N/A
8497658	12/2012	Von Novak	N/A	N/A
8554165	12/2012	Liu et al.	N/A	N/A
8587154	12/2012	Fells	N/A	N/A
8618770	12/2012	Baarman	N/A	N/A
8766484	12/2013	Baarman et al.	N/A	N/A
8829732	12/2013	Tengner	N/A	N/A
8830036	12/2013	Park	N/A	N/A
8855554	12/2013	Cook	N/A	N/A
8884468	12/2013	Lemmens	N/A	N/A
8912686	12/2013	Stoner, Jr.	N/A	N/A
8928284	12/2014	Carobolante	N/A	N/A
9084343	12/2014	Waffenschmidt	N/A	N/A
9178376	12/2014	Jung	N/A	N/A
9294153	12/2015	Muratov	N/A	N/A
9356473	12/2015	Ghovanloo	N/A	N/A
9407327	12/2015	Kirby et al.	N/A	N/A
9793738	12/2016	Jacobs et al.	N/A	N/A
9795069	12/2016	Waffenschmidt	N/A	N/A
11601017	12/2022	Partovi	N/A	N/A
12046414	12/2023	Partovi	N/A	N/A
2002/0004167	12/2001	Jenson	N/A	N/A
2002/0045454	12/2001	Iwata	N/A	N/A
2002/0067238	12/2001	Leu	N/A	N/A
2002/0089305	12/2001	Park	N/A	N/A
2002/0093309	12/2001	Peele	N/A	N/A
2003/0025417	12/2002	Rose	N/A	N/A
2003/0094921	12/2002	Lau	N/A	N/A
2003/0095027	12/2002	Shu Yuen Hui	N/A	N/A
2003/0103039	12/2002	Burr	N/A	N/A
2003/0195581	12/2002	Meadows	N/A	N/A
2003/0210106	12/2002	Cheng	N/A	N/A
2003/0214255	12/2002	Baarman	N/A	N/A
2004/0113589	12/2003	Crisp	N/A	N/A
2004/0130915	12/2003	Baarman	N/A	N/A
2004/0130916	12/2003	Baarman	N/A	N/A
2004/0145342	12/2003	Lyon	N/A	N/A
2004/0145343	12/2003	Naskali	N/A	N/A
2004/0150934	12/2003	Baarman et al.	N/A	N/A
2004/0222751	12/2003	Mollema	N/A	N/A
2004/0232845	12/2003	Baarman	N/A	N/A
2005/0007067	12/2004	Baarman	N/A	N/A
2005/0017677	12/2004	Burton	N/A	N/A
2005/0062567	12/2004	Zimmerling et al.	N/A	N/A
2005/0063488	12/2004	Troyk	N/A	N/A
2005/0068019	12/2004	Nakamura et al.	N/A	N/A
2005/0075696	12/2004	Forsberg	N/A	N/A

2005/0093475	12/2004	Kuennen	N/A	N/A
2005/0116650	12/2004	Baarma	N/A	N/A
2005/0116683	12/2004	Cheng	N/A	N/A
2005/0122058	12/2004	Baarma	N/A	N/A
2005/0122059	12/2004	Baarma	N/A	N/A
2005/0127849	12/2004	Baarma	N/A	N/A
2005/0127850	12/2004	Baarma	N/A	N/A
2005/0127866	12/2004	Hamilton	N/A	N/A
2005/0127867	12/2004	Calhoon	N/A	N/A
2005/0127869	12/2004	Calhoon	N/A	N/A
2005/0134213	12/2004	Takagi	N/A	N/A
2005/0135122	12/2004	Cheng	N/A	N/A
2005/0140482	12/2004	Cheng	N/A	N/A
2005/0162125	12/2004	Yu	N/A	N/A
2005/0189910	12/2004	Shu-yuen	N/A	N/A
2005/0257855	12/2004	Kim	N/A	N/A
2005/0259448	12/2004	Koike	N/A	N/A
2005/0270745	12/2004	Chen	N/A	N/A
2005/0270805	12/2004	Yasumura	N/A	N/A
2005/0288743	12/2004	Ahn	N/A	N/A
2006/0021926	12/2005	Woodard	N/A	N/A
2006/0038794	12/2005	Schneidman	N/A	N/A
2006/0061324	12/2005	Oglesbee	N/A	N/A
2006/0105718	12/2005	Ozluturk	N/A	N/A
2006/0106965	12/2005	Falcon	N/A	N/A
2006/0108977	12/2005	Kagermeier	N/A	N/A
2006/0132045	12/2005	Baarma	N/A	N/A
2006/0146517	12/2005	Park	N/A	N/A
2006/0202665	12/2005	Hsu	N/A	N/A
2006/0205381	12/2005	Beart	N/A	N/A
2006/0238930	12/2005	Baarma	N/A	N/A
2006/0284593	12/2005	Nagy	N/A	N/A
2007/0026826	12/2006	Wilson	N/A	N/A
2007/0029965	12/2006	Hui	N/A	N/A
2007/0035917	12/2006	Hotelling et al.	N/A	N/A
2007/0069687	12/2006	Suzuki	N/A	N/A
2007/0072474	12/2006	Beasley	N/A	N/A
2007/0103110	12/2006	Sagoo	N/A	N/A
2007/0109708	12/2006	Hussman	N/A	N/A
2007/0129768	12/2006	He	N/A	N/A
2007/0133156	12/2006	Ligtenberg	N/A	N/A
2007/0139000	12/2006	Kozuma	N/A	N/A
2007/0145830	12/2006	Lee	N/A	N/A
2007/0145945	12/2006	McGinley et al.	N/A	N/A
2007/0178945	12/2006	Cook et al.	N/A	N/A
2007/0182367	12/2006	Partovi	N/A	N/A
2007/0228833	12/2006	Stevens	N/A	N/A
2007/0236174	12/2006	Kaye	N/A	N/A
2007/0252737	12/2006	Eikenbroek	N/A	N/A
2007/0279002	12/2006	Partovi	N/A	N/A

2007/0296393	12/2006	Malpas	N/A	N/A
2008/0014897	12/2007	Cook	N/A	N/A
2008/0061733	12/2007	Toya	N/A	N/A
2008/0067874	12/2007	Tseng	N/A	N/A
2008/0079392	12/2007	Baarman	N/A	N/A
2008/0164839	12/2007	Kato	N/A	N/A
2008/0211455	12/2007	Park	N/A	N/A
2008/0245851	12/2007	Kowalski	N/A	N/A
2008/0247210	12/2007	Hu	N/A	N/A
2008/0258679	12/2007	Manico	N/A	N/A
2008/0272889	12/2007	Symons	N/A	N/A
2008/0278264	12/2007	Karalis	N/A	N/A
2008/0296978	12/2007	Finkenzeller	N/A	N/A
2009/0015075	12/2008	Cook	N/A	N/A
2009/0027136	12/2008	Traa	N/A	N/A
2009/0027149	12/2008	Kocijan	N/A	N/A
2009/0033564	12/2008	Cook	N/A	N/A
2009/0043727	12/2008	Cohen. , Jr.	N/A	N/A
2009/0049554	12/2008	Vuong	N/A	N/A
2009/0058189	12/2008	Cook	N/A	N/A
2009/0058361	12/2008	John	N/A	N/A
2009/0072627	12/2008	Cook	N/A	N/A
2009/0072628	12/2008	Cook	N/A	N/A
2009/0072629	12/2008	Cook	N/A	N/A
2009/0079268	12/2008	Cook	N/A	N/A
2009/0096413	12/2008	Partovi	N/A	N/A
2009/0102292	12/2008	Cook	N/A	N/A
2009/0127937	12/2008	Widmer	N/A	N/A
2009/0134712	12/2008	Cook	N/A	N/A
2009/0167449	12/2008	Cook	N/A	N/A
2009/0174263	12/2008	Baarman et al.	N/A	N/A
2009/0179719	12/2008	Chen	N/A	N/A
2009/0195332	12/2008	Joannopoulos	N/A	N/A
2009/0195333	12/2008	Joannopoulos	N/A	N/A
2009/0212636	12/2008	Cook	N/A	N/A
2009/0212637	12/2008	Baarman et al.	N/A	N/A
2009/0212639	12/2008	Johnson	N/A	N/A
2009/0213028	12/2008	Cook	N/A	N/A
2009/0224608	12/2008	Cook	N/A	N/A
2009/0224609	12/2008	Cook	N/A	N/A
2009/0224856	12/2008	Karalis	N/A	N/A
2009/0230777	12/2008	Baarman et al.	N/A	N/A
2009/0243397	12/2008	Cook	N/A	N/A
2009/0244836	12/2008	Leng et al.	N/A	N/A
2009/0250574	12/2008	Fullerton et al.	N/A	N/A
2009/0257259	12/2008	Leibovitz	N/A	N/A
2009/0261778	12/2008	Kook	N/A	N/A
2009/0267709	12/2008	Joannopoulos	N/A	N/A
2009/0267710	12/2008	Joannopoulos	N/A	N/A
2009/0267721	12/2008	Okada	N/A	N/A

2009/0284083	12/2008	Karalis	N/A	N/A
2009/0284227	12/2008	Mohammadian	N/A	N/A
2010/0007307	12/2009	Baerman	N/A	N/A
2010/0013431	12/2009	Liu	N/A	N/A
2010/0038970	12/2009	Cook	N/A	N/A
2010/0066176	12/2009	Azancot	N/A	N/A
2010/0070219	12/2009	Azancot	N/A	N/A
2010/0072825	12/2009	Azancot	N/A	N/A
2010/0073177	12/2009	Azancot	N/A	N/A
2010/0081377	12/2009	Chatterjee	N/A	N/A
2010/0081473	12/2009	Chatterjee	N/A	N/A
2010/0083012	12/2009	Corbridge et al.	N/A	N/A
2010/0084918	12/2009	Fells	N/A	N/A
2010/0096934	12/2009	Joannopoulos	N/A	N/A
2010/0102639	12/2009	Joannopoulos	N/A	N/A
2010/0102640	12/2009	Joannopoulos	N/A	N/A
2010/0102641	12/2009	Joannopoulos	N/A	N/A
2010/0109443	12/2009	Cook	N/A	N/A
2010/0109445	12/2009	Kurs	N/A	N/A
2010/0117454	12/2009	Cook	N/A	N/A
2010/0117455	12/2009	Joannopoulos	N/A	N/A
2010/0117456	12/2009	Karalis	N/A	N/A
2010/0117596	12/2009	Cook	N/A	N/A
2010/0123353	12/2009	Joannopoulos	N/A	N/A
2010/0123354	12/2009	Joannopoulos	N/A	N/A
2010/0123355	12/2009	Joannopoulos et al.	N/A	N/A
2010/0127573	12/2009	Joannopoulos	N/A	N/A
2010/0127574	12/2009	Joannopoulos	N/A	N/A
2010/0127575	12/2009	Joannopoulos	N/A	N/A
2010/0127660	12/2009	Cook	N/A	N/A
2010/0133918	12/2009	Joannopoulos	N/A	N/A
2010/0133919	12/2009	Joannopoulos	N/A	N/A
2010/0133920	12/2009	Joannopoulos	N/A	N/A
2010/0141042	12/2009	Kesler	N/A	N/A
2010/0146308	12/2009	Gioscia et al.	N/A	N/A
2010/0148589	12/2009	Hamam	N/A	N/A
2010/0164296	12/2009	Kurs	N/A	N/A
2010/0164297	12/2009	Kurs	N/A	N/A
2010/0164298	12/2009	Karalis	N/A	N/A
2010/0171368	12/2009	Schatz	N/A	N/A
2010/0171369	12/2009	Taylor et al.	N/A	N/A
2010/0181841	12/2009	Azancot	N/A	N/A
2010/0181843	12/2009	Schatz	N/A	N/A
2010/0181845	12/2009	Fiorello	N/A	N/A
2010/0184371	12/2009	Cook	N/A	N/A
2010/0187911	12/2009	Joannopoulos	N/A	N/A
2010/0190435	12/2009	Cook	N/A	N/A
2010/0190436	12/2009	Cook	N/A	N/A
2010/0194336	12/2009	Azancot	N/A	N/A
2010/0201313	12/2009	Vorenkamp	N/A	N/A

2010/0207572	12/2009	Kirby	N/A	N/A
2010/0207771	12/2009	Trigiani	N/A	N/A
2010/0213895	12/2009	Keating	N/A	N/A
2010/0219183	12/2009	Azancot	N/A	N/A
2010/0219693	12/2009	Azancot	N/A	N/A
2010/0219697	12/2009	Azancot et al.	N/A	N/A
2010/0219698	12/2009	Azancot	N/A	N/A
2010/0230301	12/2009	Fellig	N/A	N/A
2010/0235006	12/2009	Brown	N/A	N/A
2010/0244584	12/2009	Azancot	N/A	N/A
2010/0253281	12/2009	Li	N/A	N/A
2010/0253282	12/2009	Azancot	N/A	N/A
2010/0257382	12/2009	Azancot	N/A	N/A
2010/0259401	12/2009	Azancot	N/A	N/A
2010/0277120	12/2009	Cook	N/A	N/A
2010/0277121	12/2009	Hall	N/A	N/A
2010/0314946	12/2009	Budde	N/A	N/A
2010/0327804	12/2009	Takahashi	N/A	N/A
2011/0012556	12/2010	Lai	N/A	N/A
2011/0018360	12/2010	Baarman	N/A	N/A
2011/0050164	12/2010	Partovi	N/A	N/A
2011/0057606	12/2010	Saunamaki	N/A	N/A
2011/0062793	12/2010	Azancot	N/A	N/A
2011/0074346	12/2010	Hall	N/A	N/A
2011/0090723	12/2010	Hu	N/A	N/A
2011/0095617	12/2010	Cook	N/A	N/A
2011/0115430	12/2010	Saunamaki	N/A	N/A
2011/0121660	12/2010	Azancot	N/A	N/A
2011/0157137	12/2010	Ben-Shalom	N/A	N/A
2011/0163713	12/2010	Wang	N/A	N/A
2011/0187318	12/2010	Hui	N/A	N/A
2011/0193520	12/2010	Yamazaki	N/A	N/A
2011/0202777	12/2010	Hijazi et al.	N/A	N/A
2011/0217927	12/2010	Ben-Shalom	N/A	N/A
2011/0221387	12/2010	Steigerwald	N/A	N/A
2011/0221391	12/2010	Won	N/A	N/A
2011/0222493	12/2010	Mangold	N/A	N/A
2011/0266878	12/2010	Cook	N/A	N/A
2012/0041843	12/2011	Taylor et al.	N/A	N/A
2012/0049991	12/2011	Baarman	N/A	N/A
2012/0077537	12/2011	Muratov	N/A	N/A
2012/0112552	12/2011	Baarman et al.	N/A	N/A
2012/0119588	12/2011	Baarman et al.	N/A	N/A
2012/0126745	12/2011	Partovi	N/A	N/A
2012/0146576	12/2011	Partovi	N/A	N/A
2012/0150670	12/2011	Taylor et al.	N/A	N/A
2012/0235636	12/2011	Partovi	N/A	N/A
2012/0259735	12/2011	Taylor et al.	N/A	N/A
2014/0125146	12/2013	Azancot et al.	N/A	N/A
2014/0224267	12/2013	Levitz	N/A	N/A

2014/0247004	12/2013	Kari et al.	N/A	N/A
2014/0339916	12/2013	Fells et al.	N/A	N/A
2015/0102684	12/2014	Tanaka	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1835338	12/2005	CN	N/A
2396901	12/2018	EP	N/A
408000838	12/1995	JP	N/A
2000133536	12/1999	JP	N/A
2000341885	12/1999	JP	N/A
2003045731	12/2002	JP	N/A
2003111312	12/2002	JP	N/A
2004222285	12/2003	JP	N/A
2004260917	12/2003	JP	N/A
2005006440	12/2004	JP	N/A
2006500894	12/2005	JP	N/A
2006141170	12/2005	JP	N/A
2006230032	12/2005	JP	N/A
2006246633	12/2005	JP	N/A
2008220130	12/2007	JP	N/A
2009200174	12/2008	JP	N/A
200357251	12/2003	KR	N/A
2005039445	12/2004	KR	N/A
100836634	12/2007	KR	N/A
199418683	12/1993	WO	N/A
1994028560	12/1993	WO	N/A
1996040367	12/1995	WO	N/A
1999050806	12/1998	WO	N/A
2002037641	12/2001	WO	N/A
2003096361	12/2002	WO	N/A
2003096512	12/2002	WO	N/A
2003105308	12/2002	WO	N/A
20030105311	12/2002	WO	N/A
2004026129	12/2003	WO	N/A
2004030176	12/2003	WO	N/A
2004038887	12/2003	WO	N/A
2004038888	12/2003	WO	N/A
2004055654	12/2003	WO	N/A
2004105226	12/2003	WO	N/A
2005024865	12/2004	WO	N/A
2005109597	12/2004	WO	N/A
2005109598	12/2004	WO	N/A
200601557	12/2005	WO	N/A
2006001557	12/2005	WO	N/A
2006022365	12/2005	WO	N/A
2006137747	12/2005	WO	N/A
2007015599	12/2006	WO	N/A
2008016273	12/2007	WO	N/A
2008050917	12/2007	WO	N/A

2008137996	12/2007	WO	N/A
2009047769	12/2008	WO	N/A
2009155000	12/2008	WO	N/A
2011021178	12/2010	WO	N/A
2011081461	12/2010	WO	N/A
2011156768	12/2010	WO	N/A
20110156768	12/2010	WO	N/A
2012040548	12/2011	WO	N/A
2012095850	12/2011	WO	N/A
201200116054	12/2011	WO	N/A

OTHER PUBLICATIONS

Samsung IPR 2023-01098 Petition for Inter Partes Review of U.S. Pat. No. 11,462,942, dated Jun. 30, 2023; 2,748 pages. cited by applicant

Samsung IPR 2023-01099 Petition for Inter Partes Review of U.S. Pat. No. 11,462,942, dated Jun. 30, 2023; 2,854 pages. cited by applicant

Samsung IPR 2023-01100 Petition for Inter Partes Review of U.S. Pat. No. 11,462,942, dated Jun. 30, 2023; 2,623 pages. cited by applicant

Samsung IPR 2023-01124 Petition for Inter Partes Review of U.S. Pat. No. 11,462,942, dated Jun. 30, 2023; 2,755 pages. cited by applicant

Samsung IPR 2023-01087 Petition for Inter Partes Review of U.S. Pat. No. 9,577,440, dated Jun. 27, 2023; 3,056 pages. cited by applicant

Samsung IPR 2023-01088 Petition for Inter Partes Review of U.S. Pat. No. 9,577,440, dated Jun. 27, 2023; 3, 104 pages. cited by applicant

Japanese Patent Office, Office Action for Japanese Patent Application No. 2010-507666, Mar. 9, 2015, 8 pages. cited by applicant

Japanese Patent Office, Office Action for Japanese Patent Application No. 2014-104181, Mar. 23, 2015, 14 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/830,161, Apr. 16, 2015, 24 pages. cited by applicant

Japanese Patent Office, Examiner's Reconsideration Report for Japanese Patent Application No. 2010-507666, Jul. 17, 2014, 1 page. cited by applicant

The Patent Office of the People's Republic of China, 2nd Office Action for Chinese Patent Application No. 200880023854.4, Apr. 15, 2013, 4 pages. cited by applicant

Unknown Author, System Description Wireless Power Transfer, vol. 1: Low Power Part 1: Interface Definition, Version 1.0, Jul. 2010, 83 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/829,346, Feb. 12, 2015, 10 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/829,186, Jan. 23, 2015, 12 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/828,933, Feb. 5, 2015, 11 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/352,096, Aug. 18, 2014, 14 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/708,584, Jan. 23, 2015, 25 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 12/769,586, Jun. 2, 2014, 23 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/708,520, Aug. 14, 2014, 9 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/115,811, Aug. 20, 2014, 20 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 14/135,082, Dec. 5, 2014, 14 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/708,520, Mar. 11, 2015, 10 pages. cited by applicant

International Searching Authority at the U.S. Patent and Trademark Office, International Search Report and Written Opinion for PCT International Patent Application No. PCT/US2013/078534, May 13, 2014, 11 pages. cited by applicant

International Searching Authority and Written Opinion From the U.S. Patent and Trademark Office, International Search Report and Written Opinion for PCT International Application No. PCT/US2013/069270, Apr. 4, 2014, 9 pages. cited by applicant

Hui, "A New Generation of Universal Contactless Battery Charging Platform for Portable Consumer Electronic Equipment", IEEE Transactions on Power Electronics, vol. 20, No. 3, May 2005, pp. 620-627, 8 pages. cited by applicant

Tang, et al., "Evaluation of the Shielding Effects on Printed-Circuit-Board Transformers Using Ferrite Plates and Copper Sheets", IEEE Transactions on Power Electronics, vol. 17, No. 6, Nov. 2002, pp. 1080-1088, 9 pages. cited by applicant

Liu, et al., "An Analysis of a Double-Layer Electromagnetic Shield for a Universal Contactless Battery Charging Platform", Department of Electronic Engineering City University of Hong Kong, IEEE, 2005, pp. 1767-1772, 6 pages. cited by applicant

Liu, et al., Equivalent Circuit Modeling of a Multilayer Planar Winding Array Structure for Use in a Universal Contactless Battery Charging Platform, IEEE Transactions on Power Electronics, vol. 22, No. 1, Jan. 2007, pp. 21-29, 9 pages. cited by applicant

Liu, et al., "Simulation Study and Experimental Verification of a Universal Contactless Battery Charging Platform with Localized Charging Features", IEEE Transactions on Power Electronics, vol. 22, No. 6, Nov. 2007, pp. 2202-2210, 9 pages. cited by applicant

Liu, et al., "Optimal Design of a Hybrid Winding Structure for Planar Contactless Battery Charging Platform", IEEE Transactions on Power Electronics, vol. 23, No. 1, Jan. 2008, pp. 455-463, 9 pages. cited by applicant

Karalis, et al., "Efficient Wirelss Non-Radiative Mid-Range Energy Transfer", ScienceDirect, Annals of Physics 323, 2008, pp. 34-48, 15 pages. cited by applicant

Su, et al., "Mutual Inductance Calculation of Movable Planar Coils on Parallel Surfaces", IEEE Transactions on Power Electronics, vol. 24, No. 4, Apr. 2009, pp. 1115-1124, 10 pages. cited by applicant

Hui, et al., "Careless Printed Circuit Board (PCB) Transformers—Fundamental Characteristics and Application Potential", IEEE Circuits and Systems, Vo. 11, No. 3, Third Quarter 2000, pp. 1-48, 48 pages. cited by applicant

Sekitani, et al., "A Large-Area Flexible Wireless Power Transmission Sheet Using Printed Plastic MEMS Switches and Organic Field-Effect Transistors", IEEE, Quantum-Phase Electronics Center, School of Engineering, The University of Tokyo, 2006, 4 pages. cited by applicant

Choi, et al., "A New Contactless Battery Charger for Portable Telecommunication/Computing Electronics", IEEE, School of Electronic and Electrical Engineering, Kyungpook National University, Taegu, Korea, 2011, pp. 58-59 2 pages. cited by applicant

Hui, et al., "Careless Printed Circuit Board (PCB) Transformers for Power MOSFET/IGBT Gate Drive Circuits", IEEE Transactions on Power Electronics, vol. 14, No. 3, May 1999, pp. 422-430, 9 pages. cited by applicant

Tang, et al., "Careless Planar Printed-Circuit-Board (PCB) Transformers—a Fundamental Concept for Signal and Energy Transfer", IEEE Transactions on Power Electronics, vol. 15, No. 5, Sep. 2000, pp. 931-941, 11 pages. cited by applicant

Hatanaka et al., "Power Transmission of a Desk with Cord-Free Power Supply". IEEE Transactions on Magnetics. vol. 38. No. 5, Sep. 2002, pp. 3329-3331, 3 pages. cited by applicant

Fernandez, et al., "Design Issues of a Core-less Transformer for a Contact-less Application", IEEE, Universidad Politecnica de Madrid, 2002, pp. 339-345, 7 pages. cited by applicant

Office Action in connection with Application No. 113/155,811 dated Mar. 8, 2013, 13 pages. cited by applicant

Liu, et al., "Optimal Design of a Hybrid Winding Structure for Planar Contactless Battery Charging Platform", IEEE, Department of Electronic Engineering, City University of Hong Kong, 2006, pp. 2568-2575, 8 pages. cited by applicant

Topfer, et al., "Multi-Pole Magnetization of NdFeB Sintered Magnets and Thick Films for Magnetic Micro-Actuators", ScienceDirect, Sensor and Actuators, 2004, pp. 257-263, 7 pages. cited by applicant

Topfer, et al., "Multi-Pole Magnetization of NdFeB Magnets for Magnetic Micro-Actuators and Its Characterization with a Magnetic Field Mapping Device", ScienceDirect, Journal of Magnetism and Magnetic Materials, 2004, 124-129, 6 pages. cited by applicant

Sakamoto, et al., "A Novel High Power Converter for Non-Contact Charging with Magnetic Coupling", IEEE Transactions on Magnetics, vol. 30, No. 6, Nov. 1994, pp. 4755-4757, 3 pages. cited by applicant

Hui, et al., "Some Electromagnetic Aspects of Careless PCB Transformers", IEEE Transactions on Power Electronics, vol. 15, No. 4, Jul. 2000, pp. 805-810, 6 pages. cited by applicant

Waffenschmidt, et al., "Limitation of Inductive Power Transfer for Consumer Applications", 13th European Conference on Power Electronics and Applications, Barcelona, 2009. EPE '09. pp. 1-10, 10 pages. cited by applicant

Stokes, "Palm Strikes Back with new OS, Pre Handset at CES, <http://arstechnica.com/news.ars/post/20090101-palm-laundhes-new-handset-pre-operating>", Jan. 8, 2009, 6 pages. cited by applicant

Sullivan, Visteon to Sell Wireless Gadget Charger, "Wire-Free Technology will Lets Consumers Dump Cords and Chargers", Red Herring, Dec. 29, 2006, 2 pages. cited by applicant

Kim, "Wireless Charger for New Palm Phone", San Francisco Chronicle and SFGate.com, May 11, 2009, 2 pages. cited by applicant

Compeau, Red Zen Marketing, "Could This be the Mojo Behind the Palm Pre's Touchstone Charger?", <http://redzenmarketing.posterous.com/could-this-be-the-mojo-behind-the-palm-pres-t>, Jun. 5, 2009, 3 pages. cited by applicant

Fulton Innovation LLC, "The Big Story for CES 2007: The Public Debut of eCoupled Intelligent Wireless Power", ecoupled, Dec. 27, 2006, 2 pages. cited by applicant

Miller, "Palm May Make Pre Scarce", The San Jose Mercury News, Apr. 29, 2009, 1 page. cited by applicant

Murakami et al., "Consideration on Cordless Power Station Contactless Power Transmission System", IEEE Transactions on Magnets, vol. 32, No. 5, Sep. 1996, 3 pages. cited by applicant

Epson Air Trans "Wireless Power Transfer", http://www.2k1.co.uk/components/epson_airtrans.asp, Dec. 8, 2008, 2 pages. cited by applicant

Choi, et al., "A New Contactless Battery Charger for Portable Telecommunication/Computing Electronics", IEEE, School of Electronic and Electrical Engineering, Kyungpook National University, Taegu, Korea, 2001, pp. 58-59 2 pages. cited by applicant

PCT International Preliminary Report on Patentability dated Nov. 10, 2011 in re International Application No. PCT,US2010/032845, 7 pages. cited by applicant

USPTO; Non-Final Action for U.S. Appl. No. 17/492,083 dated Apr. 11, 2022, 30 pages. cited by applicant

USPTO; Non-Final Action for U.S. Appl. No. 17/492,083 dated Dec. 8, 2021 79 pages. cited by applicant

PCT International Search Report in connection with PCT application No. PCT/US2007/61406, 8 pages, dated Feb. 14, 2008. cited by applicant

PCT International Search Report in connection with PCT application No. PCT/US2008/63084, 8 pages, dated Aug. 8, 2008. cited by applicant

Office Action in connection with U.S. Appl. No. 13/442,698 dated Sep. 13, 2012, 6 pages. cited by applicant

Office Action in connection with U.S. Appl. No. 12/116,876 dated May 2, 2011, 5 pages. cited by applicant

Office Action in connection with U.S. Appl. No. 11/669,113 dated May 13, 2010, 20 pages. cited by applicant

Office Action in connection with U.S. Appl. No. 11/669,113 dated Aug. 25, 2009, 17 pages. cited by applicant

Office Action in connection with U.S. Appl. No. 11/669,113 dated Oct. 29, 2008, 11 pages. cited by applicant

Office Action in connection with U.S. Appl. No. 13/113,977 dated Nov. 9, 2012, 9 pages. cited by applicant

International Search Report and Written Opinion of the International Searching Authority, Korean Intellectual Property Office, in re International Application No. PCT/US2010/032845 dated Dec. 13, 2010, 10 pages. cited by applicant

WildCharge Life unplugged!. <http://www.wildcharg.com/4/17/2009>, 2 pages. cited by applicant

Powermat “the Future of Wireless Power has Arrived”, <http://www.pwrml.com>, Apr. 15, 2009, 2 pages. cited by applicant

ECoupled Wireless Power Technology Fulton Innovation, <http://www.ecoupled.com>, Apr. 15, 2009, 5 pages. cited by applicant

Qualcomm Products and Services—Wireless Airlink Technologies, http://www.qualcomm.com/products_services/airlinks, Apr. 15, 2009, 4 pages. cited by applicant

Office Action in connection with U.S. Appl. No. 11/757,067 dated Jan. 26, 2009, 14 pages. cited by applicant

Office Action in connection with U.S. Appl. No. 11/757,067 dated Oct. 19, 2009, 14 pages. cited by applicant

Office Action in connection with U.S. Appl. No. 11/757,067 dated May 10, 2010, 15 pages. cited by applicant

Wipower, Wikipedia, the free encyclopedia, <http://en.wikipedia.org/wiki/WiPower>, Nov. 18, 2011, 2 pages. cited by applicant

Powerbyproxi, Wireless Power Solutions, <http://www.powerbyproxi.com/>, Nov. 18, 2011, 2 pages. cited by applicant

Now charge your iPhone 4 and 4S with Powermat!, Wireless charging mats and receivers for your iPhone, iPod, Blackberry . . . <http://www.powermat.com/>, Nov. 18, 2011, 1 page. cited by applicant

Witricity. Wireless Electricity Delivered Over Distance, <http://www.witricity.com>, Nov. 18, 2011, 1 page. cited by applicant

ConvenientPower, ConvenientPower HK Limited, <http://www.convenientpower.com/1/about.php>, Nov. 18, 2011, 1 page. cited by applicant

Nigel Power LLC: Private Company Information—Business Week, <http://investing.businessweek.com/research/stocks/private/snapshot.asp? p . . .>, Nov. 18, 2011, 2 pages. cited by applicant

Sakamoto, et al., “A Novel Circuit for Non-Contact Charging Through Electro-Magnetic Coupling”, 1992, IEEE, pp. 165-174. cited by applicant

Abe, et al., “A Non-Contact Charger Using a Resonant Converter with Parallel Capacitor of the Secondary Coil”, Apr. 2000, IEEE, Vol. 36, No. 2, pp. 444-451. cited by applicant

Sakamoto, et al. “Large Air-Gap Coupler for Inductive Charger”, Sep. 1999, IEEE, vol. 35, No. 5,

pp. 3526-3528. cited by applicant

Sakamoto, et al. "A Novel Converter for Non-Contact Charging with Electromagnetic Coupling", Nov. 1993, IEEE, vol. 29, No. 6, pp. 3228-3230. cited by applicant

Kim, et al. "Design of a Contactless Battery Charger for Cellular Phone", Dec. 2001, IEEE, vol. 48, No. 6, pp. 1238-1247. cited by applicant

Hui, et al. "Careless Printed-Circuit Board Transformers for Signal and Energy Transfer", Electronics Letters, May 1998, vol. 34, No. 11, pp. 1052-1054. cited by applicant

Hui, et al. "Optimal Operation of Careless PCB Transformer-Isolated Gate Drive Circuits with Wide Switching Frequency Range", May 1999, IEEE Transactions of Power Electronics, vol. 14, No. 3, pp. 506-514. cited by applicant

Tang, et al. "Characterization of Careless Printed Circuit Board (PCB) Transformers", Nov. 2000, IEEE Transactions of Power Electronics, vol. 15, No. 6, pp. 1275-1282. cited by applicant

Tang, et al. "Careless Printed Circuit Board (PCB) Transformers with Multiple Secondary Windings for Complementary Gate Drive Circuits", May 1999, IEEE Transactions of Power Electronics, vol. 14, No. 3, pp. 431-437. cited by applicant

Tang, et al. "Careless Printed Circuit Board (PCB) Transformers with High Power Density and High Efficiency", May 2000, Electronics Letters, vol. 36, No. 11, pp. 943-944. cited by applicant

Borenstein, "Man Tries Wirelessly Boosting Batteries", Nov. 2006, USA Today, http://www.usatoday.com/tech/wireless/data/2006-11-16-wireless-recharging_x.htm, 5 pages. cited by applicant

Murph, "WildCharger Charges Your Gadgets Sans Wires", Dec. 2006, Misc. Gadgets, 2 pages. cited by applicant

Gizmo Watch, "Pitstop: a Table Top Recharging Solution by Belkin", <http://www.gizmowatch.com/entry/pitstop-a-table-top-recharging-solution-by-belkin>, Dec. 2006, 5 pages. cited by applicant

Unknown Author, "Cutting the Cord", Apr. 2007, The Economist, 1 page. cited by applicant

Bishop, "Microsoft Surface Brings Computing to the Table", May 2007, http://seattlepi.nwsource.com/business/317737_msftdevic30.html, 7 pages. cited by applicant

Wildcharge, "The Wire-Free Power Revolution is Only Days Away, and WildCharge, Inc. Is Leading the Charge", Sep. 2007, 3 pages. cited by applicant

Economist.com Science Technology Quarterly, "Wireless Charging", http://www.economist.com/science/tq/PrinterFriendly.cfm?story_id=13174387, Apr. 15, 2009, 4 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/708,548, Nov. 20, 2013, 5 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/115,811, Sep. 23, 2013, 17 pages. cited by applicant

United States Patent and Trademark Office. Office Action for U.S. Appl. No. 13/708,584, Sep. 13, 2013, 16 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/158,134 Jan. 22, 2014, 43 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/708,827, Feb. 5, 2014, 28 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/708,520, Feb. 5, 2014, 8 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/115,811, Mar. 4, 2014, 15 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/709,983, Feb. 27, 2014, 10 pages. cited by applicant

United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/710,062, Feb. 27,

2014, 9 pages. cited by applicant
United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/710,017, Feb. 27, 2014, 11 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 13/708,520 dated May 24, 2013, 7 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 13/158,134 dated Jun. 12, 2013, 15 pages. cited by applicant
United States Patent and Trademark Office, Office Action for U.S. Appl. No. 13/708,838, Mar. 14, 2014, 30 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 13/709,983 dated Jun. 7, 2013, 7 pages. cited by applicant
International Search Report dated Jun. 14, 2013, International Application No. PCT/US2013/033352 filed Mar. 21, 2013, 3 pages. cited by applicant
International Searching Authority, International Search Report and Written Opinion for PCT/US2012/021729, Aug. 31, 2012, 9 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 13/710,017 dated Jun. 11, 2013, 7 pages. cited by applicant
European Search Report and Search Opinion in connection with Europe Application 08747863.2 (European National Stage application of PCT/US2008/063084) dated Apr. 2, 2013, 7 pages. cited by applicant
Office Action in connection with Chinese Application 200880023854.4 (Chinese National Stage application of PCT/US2008/063084) dated Aug. 28, 2012, 18 pages. cited by applicant
Office Action in connection with Japanese Application JP/2010-50766 (Japanese National Stage application of PCT/US2008/063084) dated Dec. 3, 2012, 4 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 13/709,937 dated Sep. 12, 2013, 7 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 12/769,586 dated Dec. 13, 2012, 19 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 13/708,827 dated Jun. 26, 2013, 22 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 13/708,838 dated Jun. 24, 2013, 27 pages. cited by applicant
PCT International Search Report in connection with PCT Application No. PCT/US2011/040062 dated Feb. 17, 2012, 9 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 13/708,548 dated Jun. 7, 2013, 5 pages. cited by applicant
Office Action in connection with U.S. Appl. No. 13/115,811 dated Mar. 28, 2013, 13 pages. cited by applicant
Samsung IPR 2023-01101 Petition for Inter Partes Review of U.S. Pat. No. 11,342,777, dated Jun. 29, 2023; 4,309 pages. cited by applicant
Samsung IPR 2023-01102 Petition for Inter Partes Review of U.S. Pat. No. 11,342,777, dated Jun. 29, 2023; 4,392 pages. cited by applicant
Defendants' Invalidity Contentions, *Mojo Mobility Inc.*, Plaintiff v. *Samsung Electronics Co., Ltd.*; *Samsung Electronics America, Inc.*, Defendants, Civil Action No. 2:22-cv-00398-JRG-RSP, dated Apr. 25, 2023, 50 pages. cited by applicant
Exhibit A of Defendants' Invalidity Contentions, *Mojo Mobility Inc.*, Plaintiff v. *Samsung Electronics Co., Ltd.*; *Samsung Electronics America, Inc.*, Defendants, Civil Action No. 2:22-cv-00398-JRG-RSP, dated Apr. 25, 2023, 1034 pages. cited by applicant
Exhibit B of Defendants' Invalidity Contentions, *Mojo Mobility Inc.*, Plaintiff v. *Samsung Electronics Co., Ltd.*; *Samsung Electronics America, Inc.*, Defendants, Civil Action No. 2:22-cv-

00398-JRG-RSP, dated Apr. 25, 2023, 1395 pages. cited by applicant
Exhibit C of Defendants' Invalidity Contentions, *Mojo Mobility Inc.*, Plaintiff v. *Samsung Electronics Co., Ltd.*; *Samsung Electronics America, Inc.*, Defendants, Civil Action No. 2:22-cv-00398-JRG-RSP, dated Apr. 25, 2023, 2336 pages. cited by applicant
Exhibit D of Defendants' Invalidity Contentions, *Mojo Mobility Inc.*, Plaintiff v. *Samsung Electronics Co., Ltd.*; *Samsung Electronics America, Inc.*, Defendants, Civil Action No. 2:22-cv-00398-JRG-RSP, dated Apr. 25, 2023, 5980 pages. cited by applicant
Exhibit E of Defendants' Invalidity Contentions, *Mojo Mobility Inc.*, Plaintiff v. *Samsung Electronics Co., Ltd.*; *Samsung Electronics America, Inc.*, Defendants, Civil Action No. 2:22-cv-00398-JRG-RSP, dated Apr. 25, 2023, 5232 pages. cited by applicant
Exhibit F of Defendants' Invalidity Contentions, *Mojo Mobility Inc.*, Plaintiff v. *Samsung Electronics Co., Ltd.*; *Samsung Electronics America, Inc.*, Defendants, Civil Action No. 2:22-cv-00398-JRG-RSP, dated Apr. 25, 2023, 751 pages. cited by applicant
Exhibit G of Defendants' Invalidity Contentions, *Mojo Mobility Inc.*, Plaintiff v. *Samsung Electronics Co., Ltd.*; *Samsung Electronics America, Inc.*, Defendants, Civil Action No. 2:22-cv-00398-JRG-RSP, dated Apr. 25, 2023, 999 pages. cited by applicant
Exhibit H of Defendants' Invalidity Contentions, *Mojo Mobility Inc.*, Plaintiff v. *Samsung Electronics Co., Ltd.*; *Samsung Electronics America, Inc.*, Defendants, Civil Action No. 2:22-cv-00398-JRG-RSP, dated Apr. 25, 2023, 4531 pages. cited by applicant
Samsung IPR 2023-01089 Petition for Inter Partes Review of U.S. Pat. No. 11,292,349, dated Jun. 27, 2023; 2,228 pages. cited by applicant
Samsung IPR 2023-01090 Petition for Inter Partes Review of U.S. Pat. No. 11,292,349, dated Jun. 27, 2023; 2,390 pages. cited by applicant
USPTO, Non-Final Office Action for U.S. Appl. No. 18/158,381, dated Mar. 21, 2024, 15 pages. cited by applicant
USPTO, Final Office Action for U.S. Appl. No. 18/181,518, dated May 22, 2024, 35 pages. cited by applicant
USPTO, Patent Board Decision for U.S. Appl. No. 17/492,083, dated Dec. 23, 2024, 11 pages. cited by applicant
USPTO, Patent Board Decision for U.S. Appl. No. 17/522,367, dated Dec. 23, 2024, 12 pages. cited by applicant
A Contactless Electrical Energy Transmission System, Feb. 1999, IEEE, Pedder. cited by applicant
DOE Fundamentals Handbook Electrical Science, FSC-6910, vol. 1, DOE-HDBK-1011/1-92, U.S. Department of Energy, Jun. 1992. cited by applicant
Finite element simulation of a universal contactless battery charging platform, Jun. 27, 2005, IEEE, Liu. cited by applicant
Physics, Henry Semat et al., Rinehart & Co., Inc., 1958, Chapters 29-32 (“Semat”). cited by applicant
Power Transmission of a Desk With a Cord-Free Power Supply, Sep. 2002, IEEE, Hatanaka. cited by applicant
Printed Circuit Board Windings—Based Ultra Low-Profile Power Conditioning Circuits for SDR Application Systems, 2005, School of Electrical Engineering and Computer Science Kyungpook National University, Lim. cited by applicant
Qi 1.0.1 Wireless Power Transfer Specification, Oct. 2010, Wireless Power Consortium. cited by applicant
The Qi Wireless Power Standard, 2010, IEEE, Wageningen. cited by applicant
USPTO, Decision on Appeal for U.S. Appl. No. 17/492,083, Appeal No. 2023-003385, dated Dec. 23, 2024, 11 pages. cited by applicant
USPTO, Non-Final Office Action for U.S. Appl. No. 18/189,468, mailed Jun. 15, 2023, 12 pages. cited by applicant

USPTO, Non-Final Office Action for U.S. Appl. No. 18/181,518, mailed Aug. 9, 2023, 15 pages. cited by applicant

USPTO, Non-Final Office Action for U.S. Appl. No. 18/179,221, mailed Oct. 3, 2023, 34 pages. cited by applicant

USPTO, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314 in *Samsung Electronics Co., Ltd.*, Petitioner, v. *Mojo Mobility Inc.*, Patent Owner, IPR2023-01091, U.S. Pat. No. 11,201,500 B2, dated Jan. 8, 2024, 55 pages. cited by applicant

USPTO, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314 in *Samsung Electronics Co., Ltd.*, Petitioner, v. *Mojo Mobility Inc.*, Patent Owner, IPR2023-01092, U.S. Pat. No. 11,201,500 B2, dated Jan. 8, 2024, 53 pages. cited by applicant

USPTO, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314 in *Samsung Electronics Co., Ltd.*, Petitioner, v. *Mojo Mobility Inc.*, Patent Owner, IPR2023-01093, U.S. Pat. No. 11,201,500 B2, dated Jan. 8, 2024, 55 pages. cited by applicant

USPTO, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314 in *Samsung Electronics Co., Ltd.*, Petitioner, v. *Mojo Mobility Inc.*, Patent Owner, IPR2023-01096, U.S. Pat. No. 11,316,371 B1, dated Feb. 6, 2024, 29 pages. cited by applicant

USPTO, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314 in *Samsung Electronics Co., Ltd.*, Petitioner, v. *Mojo Mobility Inc.*, Patent Owner, IPR2023-01095, U.S. Pat. No. 11,316,371 B1, dated Feb. 9, 2024, 21 pages. cited by applicant

USPTO, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314 in *Samsung Electronics Co., Ltd.*, Petitioner, v. *Mojo Mobility Inc.*, Patent Owner, IPR2023-01094, U.S. Pat. No. 11,316,371 B1, dated Feb. 9, 2024, 31 pages. cited by applicant

USPTO, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314 in *Samsung Electronics Co., Ltd.*, Petitioner, v. *Mojo Mobility Inc.*, Patent Owner, IPR2023-01097, U.S. Pat. No. 11,316,371 B1, dated Feb. 9, 2024, 21 pages. cited by applicant

USPTO, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314 in *Samsung Electronics Co., Ltd.*, Petitioner, v. *Mojo Mobility Inc.*, Patent Owner, IPR2023-01086, U.S. Pat. No. 7,948,208 B2, dated Feb. 13, 2024, 24 pages. cited by applicant

Samsung IPR 2023-01086 Petition for Inter Partes Review of U.S. Pat. No. 7,948,208, dated Jun. 27, 2023; 2,826 pages. cited by applicant

Samsung IPR 2023-01091 Petition for Inter Partes Review of U.S. Pat. No. 11,201,500, dated Jun. 28, 2023; 2,843 pages. cited by applicant

Samsung IPR 2023-01092 Petition for Inter Partes Review of U.S. Pat. No. 11,201,500, dated Jun. 28, 2023; 2,756 pages. cited by applicant

Samsung IPR 2023-01093 Petition for Inter Partes Review of U.S. Pat. No. 11,201,500, dated Jun. 28, 2023; 2,724 pages. cited by applicant

USPTO; Final Action for U.S. Appl. No. 17/492,083 dated Aug. 15, 2022, 29 pages. cited by applicant

Samsung IPR 2023-01094 Petition for Inter Partes Review of U.S. Pat. No. 11,316,371, dated Jun. 30, 2023; 2,313 pages. cited by applicant

Samsung IPR 2023-01095 Petition for Inter Partes Review of U.S. Pat. No. 11,316,371, dated Jun. 30, 2023; 3,164 pages. cited by applicant

Samsung IPR 2023-01096 Petition for Inter Partes Review of U.S. Pat. No. 11,316,371, dated Jun. 30, 2023; 2,872 pages. cited by applicant

Samsung IPR 2023-01097 Petition for Inter Partes Review of U.S. Pat. No. 11,316,371, dated Jun. 30, 2023; 2,799 pages. cited by applicant

Final Judgement, *Mojo Mobility Inc. v. Samsung Elecs. Co., Ltd.*, Case No. 2:22-CV-00398, Mar. 20, 2025, 3 pages. cited by applicant

Samsung Electronics Co., Ltd. (Petitioner) v. *Mojo Mobility Inc.* (Patent Owner), Petition for Inter Partes Review of U.S. Pat. No. 11,342,777, IPR2023-01101, dated Jun. 29, 2023, 86 pages. cited

by applicant

Samsung Electronics Co., Ltd. (Petitioner) v. Mojo Mobility Inc. (Patent Owner), Petition for Inter Partes Review of U.S. Pat. No. 11,342,777, IPR2023-01102, dated Jun. 29, 2023, 89 pages. cited by applicant

USPTO, *Samsung Electronics Co., Ltd. (Petitioner) v. Mojo Mobility Inc. (Patent Owner)*, IPR2023-01101, U.S. Pat. No. 11,342,777 B2, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314, dated Jan. 10, 2024, 23 pages. cited by applicant

USPTO, *Samsung Electronics Co., Ltd. (Petitioner) v. Mojo Mobility Inc. (Patent Owner)*, IPR2023-01102, U.S. Pat. No. 11,342,777 B2, Decision Denying Institution of Inter Partes Review 35 U.S.C. §314, dated Jan. 10, 2024, 23 pages. cited by applicant

Exhibit PA-DEC, Declaration of R. Jacob Baker, Ph.D., P.E., In support of Ex Parte Reexamination of U.S. Pat. No. 11,342,777, dated Jun. 27, 2024, 111 pages. cited by applicant

Request for Ex Parte Reexamination of U.S. Pat. No. 11,342,777, Reexam No. U.S. Appl. No. 90/019,558, dated Jun. 28, 2024, 43 pages. cited by applicant

USPTO, Non-Final Office Action for U.S. Appl. No. 18/756,718, dated Jun. 17, 2025, 19 pages. cited by applicant

USPTO, Non-Final Office Action in Ex Parte Reexamination No. U.S. Appl. No. 90/019,558, dated Apr. 10, 2025, 61 pages. cited by applicant

USPTO, Non-Final Office Action in Ex Parte Reexamination No. U.S. Appl. No. 90/019,558, dated Dec. 13, 2024, 45 pages. cited by applicant

Primary Examiner: Tso; Edward

Assistant Examiner: Omar; Ahmed H

Attorney, Agent or Firm: NK Patent Law

Background/Summary

CLAIM OF PRIORITY AND CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 17/522,367, titled “MAGNETIC STRUCTURE WITH MULTIPLE OPPOSING POLES ON A SURFACE FOR USE WITH MAGNETICALLY SENSITIVE COMPONENTS”, filed Nov. 9, 2021 and being issued as U.S. Pat. No. 12,293,872 on May 6, 2025, which is a continuation of U.S. patent application Ser. No. 17/492,083, titled “MAGNET WITH MULTIPLE OPPOSING POLES ON A SURFACE FOR USE WITH MAGNETICALLY SENSITIVE COMPONENTS”, filed Oct. 1, 2021, and subsequently issued on Apr. 15, 2025 as U.S. Pat. No. 12,278,045, which is a continuation of U.S. patent application Ser. No. 16/538,452, titled “MAGNET WITH MULTIPLE OPPOSING POLES ON A SURFACE FOR USE WITH MAGNETICALLY SENSITIVE COMPONENTS”, filed Aug. 12, 2019, and subsequently issued on Mar. 22, 2022 as U.S. Pat. No. 11,283,306, which is a continuation of U.S. patent application Ser. No. 14/556,760, titled “INTELLIGENT INITIATION OF INDUCTIVE CHARGING PROCESS”, filed Dec. 1, 2014, and subsequently issued on Jul. 14, 2020 as U.S. Pat. No. 10,714,986, which is a continuation of U.S. patent application Ser. No. 13/708,838, titled “INTELLIGENT INITIATION OF INDUCTIVE CHARGING PROCESS”, filed Dec. 7, 2012, and subsequently issued on Dec. 2, 2014 as U.S. Pat. No. 8,901,881; which is a continuation of U.S. patent application Ser. No. 13/158,134, titled “SYSTEM FOR WIRELESS POWER TRANSFER THAT SUPPORTS INTEROPERABILITY, AND MULTI-POLE MAGNETS FOR USE THEREWITH”, filed Jun. 10, 2011, and subsequently issued on Nov. 18, 2014 as U.S. Pat. No. 8,890,470; which application claims the benefit of priority to U.S.

Provisional Patent Application No. 61/478,015, titled "SYSTEM AND METHOD FOR PROVIDING A UNIVERSAL-COMPATIBLE WIRELESS POWER SYSTEM", filed Apr. 21, 2011; U.S. Provisional Patent Application No. 61/387,895, titled "SYSTEM AND METHOD FOR PROVIDING A UNIVERSAL-COMPATIBLE WIRELESS POWER SYSTEM", filed Sep. 29, 2010; and U.S. Provisional Patent Application No. 61/354,114, titled "IMPROVED MAGNETS FOR USE IN PROXIMITY TO MAGNETICALLY SENSITIVE PARTS OR DEVICES", filed Jun. 11, 2010; which application is related to U.S. patent application Ser. No. 11/669,113, titled "INDUCTIVE POWER SOURCE AND CHARGING SYSTEM", filed Jan. 30, 2007 (subsequently published as U.S. Publication No. 20070182367, and issued as U.S. Pat. No. 7,952,322); U.S. patent application Ser. No. 11/757,067, titled "POWER SOURCE, CHARGING SYSTEM, AND INDUCTIVE RECEIVER FOR MOBILE DEVICES", filed Jun. 1, 2007 (subsequently published as U.S. Publication No. 20070279002, and issued as U.S. Pat. No. 7,948,208); U.S. patent application Ser. No. 12/116,876, titled "SYSTEM AND METHOD FOR INDUCTIVE CHARGING OF PORTABLE DEVICES", filed May 7, 2008 (subsequently published as U.S. Publication No. 20090096413); and U.S. patent application Ser. No. 12/769,586, titled "SYSTEM AND METHODS FOR INDUCTIVE CHARGING, AND IMPROVEMENTS AND USES THEREOF", filed Apr. 28, 2010 (subsequently published as U.S. Publication No. 20110050164); each of which above applications are herein incorporated by reference.

COPYRIGHT NOTICE

(1) A portion of the disclosure of this patent document contains material which is subject to copyright protection. The copyright owner has no objection to the facsimile reproduction by anyone of the patent document or the patent disclosure, as it appears in the Patent and Trademark Office patent file or records, but otherwise reserves all copyright rights whatsoever.

FIELD OF INVENTION

(2) The invention is generally related to inductive charging, including applications for use in mobile or other devices and vehicles, and improved compatibility and transfer of wireless power; and is also related to the use of magnets in electronic devices, and in particular to devices or parts having proximity to magnetic sensors.

BACKGROUND

(3) Wireless technologies for powering and charging mobile and other electronic devices and vehicles have been developed. These systems generally use a wireless charger or transmitter system and a wireless receiver in combination to provide a means for transfer of power across a distance. For safe and efficient operation the two parts of the system often communicate with each other to verify the presence of receivers and/or initiate charging and continued power transfer. To enable interoperability between chargers and receivers, it is important that the two parts of the system (the charger and the receiver) can communicate in a manner that allows such operation.

(4) Additionally, many mobile, industrial, automotive, medical devices, etc. contain compasses or other components that are sensitive to magnetic field. At the same time, it is often desired to use magnets for fastening or attachment, or alignment purposes near such devices without affecting the operation of such sensitive material. One application may be fastening of a mobile device or phone to a surface in a car or other vehicle to avoid movement during transport.

(5) These are the general areas that embodiments of the invention are intended to address.

SUMMARY

(6) As described above, to enable interoperability between chargers and receivers, it is important that the two parts of the system (the charger and receiver) can communicate in a manner that allows operation. With the proliferation of different communication schemes, a multi-protocol system that can adapt and interoperate with different communication protocols allows maximum interoperability. Described herein are systems and methods for providing such multi-protocol operation and maximum interoperability. Also described herein are methods for use of magnets in

or around magnetically sensitive devices such that the operation of such a device is not impaired. Applications in various devices and systems are described. In particular, applications for fastening mobile devices to their cases or other surfaces, and also alignment or attachment for power transfer or charging are described. Also described herein are systems and methods for the use of multi-pole and other magnets, in electronic and other articles, devices, components, or parts thereof.

(7) According to one embodiment, an inductive charger for inductive charging a battery in an electronic device having a substantially planar receiver coil is disclosed. The inductive charger includes a substantially planar inductive charger coil comprising Litz wire wound in a substantially spiral shape for generating an alternating magnetic field substantially perpendicular to the plane of the inductive charger coil to transfer inductive power to the receiver coil in the electronic device for charging the battery in the electronic device. The inductive charger further includes a magnetic structure configured to generate a magnetic field that creates a magnetic attachment between the inductive charger and the electronic device and to align the inductive charger coil with the receiver coil of the electronic device for inductive power transfer for charging the battery in the electronic device, the magnetic structure comprising two or more discontinuous arc-shaped permanent magnet sections that define a substantially flat first surface and a substantially flat second surface opposite the first surface. Each magnetic section comprises at least two magnetic poles of opposite polarity located at each of the first and second surfaces of each magnetic section such that each magnetic section includes at least two pairs of opposing magnetic poles oriented to cause magnetization in two opposing directions that are each perpendicular to the first and second surfaces. The magnetic sections are assembled to form a full or partial ring shape and the magnetic structure is positioned around an outer perimeter of the inductive charger coil and is substantially concentric with the inductive charger coil. The magnetic structure is configured to create a magnetic field with flux densities having substantially similar magnitudes relative to the first and second surfaces as a function of distance from the first and second surfaces, respectively, along an axis that runs perpendicular to the first and second surfaces. The inductive charger further includes a magnetic shield layer comprising a nano-crystalline material positioned parallel to the plane of the inductive charger coil on a side of the inductive charger coil that is opposite the electronic device during inductive power transfer. The magnetic shield layer is positioned to shield a portion of the inductive charger from the alternating magnetic field while transferring the inductive power. The magnetic structure is configured such that the magnetic field generated by the magnetic structure does not impair operation of the magnetic shield layer during the inductive power transfer, and the electronic device can be rotated across a continuous range of rotational angles with respect to the inductive charger while keeping the alignment between the inductive charger coil and the inductive receiver coil during inductive power transfer for charging the battery in the electronic device.

(8) According to another embodiment, an electronic device configured for receiving inductive power from an inductive charger is disclosed. The electronic device includes a rechargeable battery to operate the electronic device. The electronic device further includes a substantially spiral shaped and substantially planar inductive charging receiver coil for receiving inductive power to charge the rechargeable battery. The inductive charging receiver coil is configured to receive an alternating magnetic field substantially perpendicular to the plane of the inductive charging receiver coil from a substantially planar charger coil in the inductive charger for receiving inductive power to charge the rechargeable battery. The electronic device further includes a magnetic structure configured to generate a magnetic field that creates a magnetic attachment between the electronic device and the inductive charger and to align the inductive charging receiver coil of the electronic device with the charger coil in the inductive charger for receiving inductive power to charge the rechargeable battery of the electronic device. The magnetic structure comprises two or more discontinuous arc-shaped permanent magnet sections that define a substantially flat first surface and a substantially flat second surface opposite the first surface. The magnetic sections are assembled to form a full or partial ring shape and the magnetic structure is positioned around an outer perimeter of the

inductive charging receiver coil and is substantially concentric with the inductive charging receiver coil. Each magnetic section is magnetized with multiple poles radially such that a first pole of the multiple poles of each magnetic section is located, relative to a second pole of the multiple poles, closer to an inner radius of the full or partial ring shape, and wherein the second pole of the multiple poles of each magnetic section is located, relative to the first pole, closer to an outer radius of the full or partial ring shape to form a magnetic field for each magnetic section that is substantially parallel to the substantially planar surface of the inductive charging receiver coil. All the magnetic sections of the magnetic structure are poled with the same orientation. The magnetic structure is configured to create a magnetic field with flux densities having substantially similar magnitudes relative to the first and second surfaces as a function of distance from the first and second surfaces, respectively, along an axis that runs perpendicular to the first and second surfaces. The electronic device further includes a magnetic shield layer comprising a nano-crystalline material positioned parallel to the plane of the inductive charging receiver coil on a side of the inductive charging receiver coil that is opposite the inductive charger while receiving inductive power. The magnetic shield layer is positioned to shield the electronic device from the alternating magnetic field while receiving the inductive power. The magnetic structure is configured such that the magnetic field generated by the magnetic structure does not impair operation of the magnetic shield layer while receiving the inductive power, and the electronic device can be rotated across a continuous range of rotational angles with respect to the inductive charger while keeping the alignment between the inductive charging receiver coil and the charger coil when receiving inductive power to charge the rechargeable battery.

(9) According to another embodiment, a stand-alone accessory device for a separate electronic device having a magnetic shield layer and a substantially planar inductive charging coil for inductive power transfer is disclosed. The accessory device includes a substantially flat magnetic structure configured to generate a magnetic field that creates a magnetic attachment to the electronic device and to align the accessory device with the electronic device. The magnetic structure comprises one or more arc-shaped permanent magnet sections that define a substantially flat first surface and a substantially flat second surface opposite the first surface. Each magnetic section includes at least two magnetic poles of opposing polarity located at each of the first and second surfaces of each magnetic section such that each magnetic section includes at least two pairs of opposing magnetic poles oriented to cause magnetization in two opposing directions that are each perpendicular to the first and second surfaces. The magnetic sections are assembled to form a full or partial ring shape and the magnetic structure is configured to be positioned, when magnetically attached to the electronic device, around an outer perimeter of the inductive charging coil and to be substantially concentric with the inductive charging coil. The magnetic field generated by the magnetic structure is configured with flux densities having substantially similar magnitudes relative to the first and second surfaces as a function of distance from the first and second surfaces, respectively, along an axis that runs perpendicular to the first and second surfaces. The magnetic structure is configured such that the magnetic structure does not impair operation of the magnetic shield layer and the electronic device.

(10) According to another embodiment, a protective case for an electronic device having a battery, a nano-crystalline magnetic shield layer, and a substantially planar inductive charging receiver coil for receiving inductive power from an inductive charger comprising a substantially planar charger coil to charge the battery is disclosed. The protective case includes a substantially flat magnetic structure configured to generate a magnetic field, the magnetic structure comprising one or more arc-shaped permanent magnet sections that define a substantially flat first surface and a substantially flat second surface opposite the first surface. The magnetic sections are assembled to form a full or partial ring shape. The magnetic structure is configured to be positioned around an outer perimeter of the inductive charging receiver coil of the electronic device and to be substantially concentric with the inductive charging receiver coil when the electronic device is

placed in the protective case. Each permanent magnet section includes at least two magnetic poles of opposing polarity located at each of the first and second surfaces of each permanent magnet section such that each permanent magnet section includes at least two pairs of opposing magnetic poles oriented to cause magnetization in two opposing directions that are each perpendicular to the first and second surfaces. The magnetic structure is configured to create a magnetic field with flux densities having substantially similar magnitudes relative to the first and second surfaces as a function of distance from the first and second surfaces, respectively, along an axis that runs perpendicular to the first and second surfaces. The magnetic structure is configured such that the electronic device, when placed in the protective case, can be rotated across a continuous range of rotational angles with respect to the inductive charger while keeping the alignment between the inductive charger coil and the inductive receiver coil while receiving inductive power from the inductive charger for inductive charging the battery in the electronic device. The magnetic structure is configured such that the magnetic field generated by the magnetic structure does not impair operation of the magnetic shield layer and the inductive charging receiver coil for receiving inductive power to charge the battery in the electronic device.

Description

BRIEF DESCRIPTION OF THE FIGURES

- (1) FIG. 1 illustrates an example of a wireless charger or power system that comprises a charger or transmitter part, and a receiver part, in accordance with an embodiment.
- (2) FIG. 2 shows a more detailed view of the wireless charger system with a resonant converter geometry, in accordance with an embodiment.
- (3) FIG. 3 illustrates a system wherein a dedicated RF channel for uni-directional or bi-directional communication between the charger and receiver is implemented for validation and/or regulation purposes, in accordance with an embodiment.
- (4) FIG. 4 illustrates the use of a center-tapped receiver wherein during each cycle current passes only through one part of the coil and one diode in the receiver and therefore halves the rectification losses, in accordance with an embodiment.
- (5) FIG. 5 illustrates that the charger and receiver coils can be represented by their respective inductances by themselves and the mutual inductance between, in accordance with an embodiment.
- (6) FIG. 6 shows a wirelessly powered battery pack and receiver, in accordance with an embodiment.
- (7) FIG. 7 illustrates the use of a battery cell connected through a protection circuit comprising a battery protection IC that protects a battery from over-current and under or over voltage, in accordance with an embodiment.
- (8) FIG. 8 illustrates a typical charge cycle for a Lithium Ion battery, in accordance with an embodiment.
- (9) FIG. 9 illustrates how the charger periodically activates the charger coil driver and powers the charger coil with a drive signal of appropriate frequency, in accordance with an embodiment.
- (10) FIG. 10 illustrates an example of the communication process and regulation of power and/or other functions, in accordance with an embodiment.
- (11) FIG. 11 shows a Notebook-style portfolio case and a mobile phone or camera pouch, where magnets are used to secure a closing clasp or flap, in accordance with an embodiment.
- (12) FIG. 12 illustrates several commercially available mounts for devices, in accordance with an embodiment.
- (13) FIG. 13 shows an example of a power plug for an electronic device, in accordance with an embodiment.
- (14) FIG. 14 shows an inductive wireless charger and/or power supply with multiple charging

stations, in accordance with an embodiment.

(15) FIG. 15 illustrates several different placements and shapes for magnets, in accordance with an embodiment.

(16) FIG. 16 shows a measured z-component along the axial direction of magnetization of a magnet, in accordance with an embodiment.

(17) FIG. 17 illustrates the performance of a 50×50×1 mm.sup.3 magnet with one of 10×10×1 mm.sup.3 dimension magnetized axially perpendicular to the square surface of the part, in accordance with an embodiment.

(18) FIG. 18 illustrates how the same shape part can be periodically poled in a multi-pole pattern, in accordance with an embodiment.

(19) FIG. 19 shows the drop off of maximum flux density value for a 10×10×1 mm.sup.3 magnet magnetized periodically with a periodicity of 1 and 2 mm, in accordance with an embodiment.

(20) FIG. 20 shows several magnet types that are magnetized perpendicular to the magnet surface (axially), in accordance with various embodiments.

(21) FIG. 21 shows an example of various ring or arc multi-pole magnets, as may be used to with a coil to provide alignment, in accordance with an embodiment.

(22) FIG. 22 illustrates a ring magnet that includes a discontinuity, in accordance with an embodiment.

(23) FIG. 23 illustrates a multi-pole ring magnet with radially magnetized sections, in accordance with an embodiment.

DETAILED DESCRIPTION

(24) With the proliferation of electrical and electronic devices and vehicles (which are considered devices herein), simple and universal methods of providing power and or charging of these devices is becoming increasingly important. To enable a user to easily charge or power these devices, a simple non-contact method such as wireless power transfer is increasingly important.

(25) Many of these devices contain internal batteries, and the device may or may not be operating during receipt of power. Depending on the degree of charge status of the battery or its presence and the system design, the applied power may provide power to the device, charge its battery or a combination of the above. The terms charging and/or power are used interchangeably herein to indicate that the received power can be used for either of these cases or a combination thereof. Unless specifically described, these terms are therefore used interchangeably.

(26) As shown in FIG. 1, a wireless charger or power system comprises a charger or transmitter part, and a receiver part. The charger or transmitter can generate a repetitive power signal pattern (such as a sinusoid or square wave from 10's of Hz to several MHz or even higher but typically in the 100 kHz to several MHz range) with its coil drive circuit and a coil or antenna for transmission of the power. The charger or transmitter typically also includes a communication and regulation/control system that detects a receiver and/or turns the applied power on or off and/or modify the amount of applied power by mechanisms such as changing the amplitude, frequency or duty cycle, etc. or a combination thereof of the applied power signal to the coil or antenna.

(27) The second part of the system is a receiver that includes a coil or antenna to receive power, a method for change of the received AC voltage to DC voltage such as rectification and smoothing with one or more rectifiers or a bridge or synchronous rectifier, etc. and one or more capacitors and optionally, a method for the receiver to communicate with the charger.

(28) In accordance with an embodiment, the method of communication between the charger and receiver can be through the same coils as for transfer of power, through a separate coil, through an RF or optical link or combination thereof. In case of communication through the power transfer coil, one method for the communication is to modulate the load in the receiver to affect the voltage in the receiver coil and therefore create a modulation in the charger coil parameters that can be detected through monitoring of its voltage or current. Other methods can include frequency modulation by combining the received frequency with a local oscillator signal or inductive,

capacitive, or resistive modulation of the output of the receiver coil.

(29) In accordance with an embodiment, the communicated information can be the output voltage, current, device or battery status, validation ID for receiver, end of charge or various charge status information, receiver battery, device, or coil temperature, or user data.

(30) In accordance with an embodiment, the data communicated can be any of the information detailed herein, or the difference between these values and the desired value or simple commands to increase or decrease power or simply one or more signals that would confirm presence of a receiver or a combination of the above. In addition, the receiver can include other elements such as a dc to dc converter or regulator such as a switching, buck, boost, buck/boost, or linear regulator. The receiver may also include a switch between the DC output of the receiver coil and its output to a device or battery or a device case or skin and in cases where the receiver is used to charge a battery, the receiver may also include a battery charger IC or circuitry and/or battery protection circuit and associated transistors, etc. The receiver and/or charger and/or their coils can also include elements such as thermistors, magnetic shields or magnetic cores, magnetic sensors, and input voltage filters, etc. for safety and/or emission compliance reasons. In addition, the charger and or receiver can include means to provide more precise alignment between the charger and receiver coils or antennas. These may include visual, physical, or magnetic means to assist the user in alignment of parts. To implement more positioning freedom of the receiver on the charger, the size of the coils can also be mismatched. For example, the charger can comprise a larger coil size and the receiver a smaller one or vice versa, so that the coils do not have to be precisely aligned for power transfer.

(31) In accordance with an embodiment, the power section (coil drive circuit and receiver power section) can be a resonant, zero switching, flyback, or any other appropriate topology. FIG. 2 shows a more detailed view of the wireless charger system with a resonant converter geometry where a pair of transistors Q1 and Q2 (such as FETs) are driven by a half-bridge driver IC and the voltage is applied to the coil L1 through one or more capacitors shown as C1. The receiver includes a coil and an optional capacitor (for added efficiency) shown as C2 that may be in series or in parallel with the receiver coil L2. The charger and/or receiver coils may also include magnetic material layers behind them to increase their inductance or to shield the magnetic field leakage to surrounding area.

(32) In accordance with an embodiment, the charger also includes a circuit that measures the current through and/or voltage across the charger coil (in this case a current sensor is shown in the figure as an example). Various demodulation methods for detection of the communication signal on the charger current or voltage are available. This demodulation mechanism can be an AM or FM receiver (depending on whether amplitude or frequency modulation is employed in the receiver modulator) similar to a radio receiver tuned to the frequency of the communication or a heterodyne detector, etc.

(33) In accordance with an embodiment, the microcontroller unit (MCU) in the charger (MCU1) is responsible for understanding the communication signal from the detection/demodulation circuit and, depending on the algorithm used, making appropriate adjustments to the charger coil drive circuitry to achieve the desired output voltage, current or power from the receiver output. In addition, MCU1 is responsible for processes such as periodic start of the charger to seek a receiver at the start of charge, keeping the charger on when a receiver is found and accepted as a valid receiver, continuing to apply power and making necessary adjustments, and/or monitoring temperature or other environmental factors, providing audio or visual indications to the user on the status of charging or power process, etc. or terminating charging or application of power due to end of charge or customer preference or over temperature, over current, over voltage, or some other fault condition or to launch or start another program or process. For example, the charger can be built into a car and once a valid receiver integrated into or on a mobile device, its case or skin, or battery is found, the charger may activate some other functions such as Bluetooth connectivity to

the device, displaying the device identity on a display, etc. Other similar actions can be done in other environments. It may be useful in addition to the communication signal to detect the dc value of the current through the charger coil. For example, faults may be caused by insertion or presence of foreign objects such as metallic materials between the charger and receiver. These materials may be heated by the application of the power and can be detected through detection of the charger current or temperature or comparison of input voltage, current, or power to the charger and output voltage, current, or power from the receiver and concluding that the ratio is out of normal range and extra power loss due to unknown reasons is occurring. In these conditions or other situations such as abnormal charger and/or receiver heating, the charger may be programmed to declare a fault condition and shut down and/or alert the user or take other actions.

(34) Once the charger MCU has received a signal and decoded this signal, it can take action to provide more or less power to the charger coil. This can be accomplished through known methods of adjusting the frequency, duty cycle or input voltage to the charger coil or a combination of these approaches. Depending on the system and the circuit used, the MCU can directly adjust the bridge driver or an additional circuit such as a frequency oscillator may be necessary to drive the bridge driver or the FETs.

(35) A typical circuit for the receiver in accordance with an embodiment, is also shown in FIG. 2. In accordance with an embodiment, the receiver circuit can include a capacitor C2 in parallel or series with the receiver coil to produce a tuned receiver circuit. This circuit is known to increase the efficiency of a wireless power system. The rectified and smoothed (through a bridge rectifier and capacitors) output of the receiver coil and optional capacitor is either directly or through a switch or regulator applied to the output. A microcontroller is used to measure various values such as output voltage, current, temperature, state of charge, battery full status, end of charge, etc. and to report back to the charger to provide a closed loop system with the charger as described above. In the circuit shown in FIG. 2, the receiver MCU communicates back to the charger by modulating the receiver load by rapidly closing and opening a switch in series with a modulation load at a pre-determined speed and coding pattern. This rapid load modulation technique at a frequency distinct from the power transfer frequency can be easily detected by the charger. A capacitor and/or inductor can also be placed in parallel or in series with this load.

(36) For example, one may assume that the maximum current output of the receiver is 1000 mA and the output voltage is 5 V for a maximum output of 5 W. In this case, the minimum load resistance is 5 ohms. A modulation load resistor of several ohms (20, or 10 ohms or smaller) would be able to provide a large modulation depth signal on the receiver coil voltage. Choosing a 5 ohm resistor would modulate the output between a maximum current of 1 Amp or larger and a smaller value defined by the device load at the output. Such a large modulation can be easily detected at the charger coil current or voltage as described above.

(37) The receiver in FIG. 2 also shows an optional dc regulator that is used to provide constant stable voltage to the receiver MCU. This voltage supply may be necessary to avoid drop out of the receiver MCU during startup conditions where the power is varying largely or during changes in output current and also to enable the MCU to have a stable voltage reference source so it can measure the output voltage accurately.

(38) In the above description, a uni-directional communication (from the receiver to the charger) is described. However, this communication can also be bi-directional and data can be transferred from the charger to the receiver through modulation of the voltage or current in the charger coil and read back by the microcontroller in the receiver detecting a change in the voltage or current, etc.

(39) In accordance with an embodiment, in other geometries where position independence on placement of the receiver on the charger surface is achieved by having multiple charger coils in an array or pattern, similar drive and communication circuits in the charger and receiver can be implemented. However, to detect the appropriate coil to activate in the charger, the coils can be activated in a raster or zigzag fashion or other geometry and current drawn from a charger coil,

strength of voltage, current, power or signal from the receiver or other methods can be used to determine the closest match between position of one or more of the charger coils and a receiver coil and the appropriate charger coil or coils can be activated and modulated to provide optimum power transfer to the receiver.

(40) While a system for communication between the charger and receiver through the power transfer coil or antenna is described above, the communication can also be implemented through a separate coil, a radio frequency link (am or fm or other communication method), an optical communication system or a combination of the above. The communication in any of these methods can also be bi-directional rather than uni-directional as described above. As an example, FIG. 3 shows a system in accordance with an embodiment, wherein a dedicated RF channel for uni-directional or bi-directional communication between the charger and receiver is implemented for validation and/or regulation purposes. This system is similar to the system shown in FIG. 2, except rather than load modulation being the method of communication, the MCU in the receiver transmits the necessary information over an RF communication path. A similar system with LED or laser transceivers or detectors and light sources can be implemented. Advantages of such system may be that the power received is not modulated and therefore not wasted during communication and/or that no noise due to the modulation is added to the system.

(41) One of the disadvantages of the circuit shown in FIG. 2 is that in the receiver circuit shown therein, the current path passes through 2 diodes and suffers 2 voltage drops resulting in large power dissipation and loss. For example, for Schottky diodes with forward voltage drop of 0.4 V, at a current output of 1 A, each diode would lose 0.4 W of power for a combined power loss of 0.8 W for the two in a bridge rectifier configuration. For a 5 V, 1 A output power (5 W), this 0.8 W of power loss presents a significant amount of loss (16%) just due to the rectification system. In accordance with an embodiment, an alternative is to use a center-tapped receiver as shown in FIG. 4 wherein during each cycle current passes only through one part of the coil and one diode in the receiver and therefore halves the rectification losses. Such a center tapped coil can be implemented in a wound wire geometry with 2 sections of a wound wire or a printed circuit board coil or with a double or multi-sided sided PCB coil or a combination or even a stamped, etched or otherwise manufactured coil or winding.

(42) In any of the systems described above, as shown in FIG. 5, the charger and receiver coils can be represented by their respective inductances by themselves (L_1 and L_2) and the mutual inductance between them M which is dependent on the material between the 2 coils and their position with respect to each other in x, y, and z dimensions. The coupling coefficient between the coils k is given by:

$$k = M / (L_1 * L_2)^{.5}$$

(43) The coupling coefficient is a measure of how closely the 2 coils are coupled and may range from 0 (no coupling) to 1 (very tight coupling). In coils with small overlap, large gap between coils or dissimilar coils (in size, number of turns, coil winding or pattern overlap, etc.), this value can be smaller than 1.

(44) FIG. 6 shows a wirelessly powered battery pack and receiver in accordance with an embodiment. The components of a typical common battery pack (battery cell and protection circuit, etc.) used in a battery device used in applications such as mobile phone, etc. are shown inside the dashed lines. The components outside the dashed lines are additional components necessary to enable safe wireless and wired charging of a battery pack. A battery pack may have four or more external connector points that interface with a mobile device pins in a battery housing or with an external typical wired charger. In accordance with an embodiment, the battery cell is connected as shown in FIG. 7 to two of these connectors (shown in the figure as Batt+ and Batt-) through a protection circuit comprising a battery protection IC that protects a battery from over-current and under or over voltage. A typical IC may be Seiko 8241 IC that uses 2 external FETs as shown in FIG. 7 to prevent current going from or to the battery cell (on the left) from the external battery

pack connectors if a fault condition based on over current, or battery cell over or under voltage is detected. This provides safety during charging or discharging of the battery. In addition, a battery pack may include a PTC conductive polymer passive fuse. These devices can sense and shut off current by heating a layer inside the PTC if the amount of current passing exceeds a threshold. The PTC device is reset once this current falls and the device cools.

(45) In addition, in accordance with an embodiment, the battery pack can contain a thermistor that the mobile device checks through one other connector on the battery pack to monitor the health of the pack, and in some embodiments an ID chip or microcontroller that the mobile device interrogates through another connector to confirm an original battery manufacturer or other information about the battery. Other connectors and functions can be included in a battery pack to provide accurate battery status and/or charging information to a device being powered by a battery pack or a charger charging the battery pack.

(46) In addition to the components described above, In accordance with an embodiment, the receiver circuit comprises a receiver coil that could be a wound wire or PCB coil as described above, optional electromagnetic shielding between the coil and the metal body of the battery, optional alignment assisting parts such as magnets, etc., a receiver communication circuit (such as the resistor and FET for load modulation shown in FIGS. 2 and 4), a wireless power receiver (such as rectifiers and capacitors as discussed above), and an optional Battery charger IC that has a pre-programmed battery charging algorithm. Each type of battery and chemistry requires a pre-determined optimized profile for charging of a battery. A typical charge cycle for a Lithium Ion (Li-Ion) is shown in FIG. 8. Such a battery may be charged up to a value of 4.2 V at full capacity. The battery should be charged according to the guidelines of the manufacturer. For a battery of capacity C, the cell can typically be charged at the rate 1C. In Stage 1, the maximum available current is applied and the cell voltage increases until the cell voltage reaches the final value (4.2 V). In that case, the charger IC switches to Stage 2 where the charger IC switches to Constant Voltage charging where the cell voltage does not change but current is drawn from the source to further fill up the battery. This second Stage may take 1 or more hours and is necessary to fully charge the battery. Eventually, the battery will draw little (below a threshold) or no current. At this stage, the battery is full and the charger may discontinue charging. The charger IC can periodically seek the condition of the battery and top it off further if the battery has drained due to stand-by, etc.

(47) Such multiple stages of battery charging may be implemented in firmware with the wireless power charger and receiver microcontrollers monitoring the battery cell voltage, current, etc. and working in tandem and to provide appropriate voltage, current, etc. for safe charging for any type of battery. In another approach as shown in FIG. 6, a battery charger IC chip that has specialized battery charging circuitry and algorithm for a particular type of battery can be employed. These charger ICs (with or without fuel gauge capability to accurately measure battery status, etc.) are available for different battery chemistries and are included in most mobile devices with mobile batteries such as mobile phones. They can include such safety features as a temperature sensor, open circuit shut off, etc. and can provide other circuits or microcontrollers such useful information as end of charge signal, signaling for being in constant current or voltage (stage 1 or 2 above, etc.). In addition, some of these ICs allow the user to program and set the maximum output current to the battery cell with an external resistor across 2 pins of the IC.

(48) In accordance with an embodiment, the wirelessly charged battery pack in addition includes a micro-controller that coordinates and monitors various points and may also include thermal sensors on the wireless power coil, battery cell and/or other points in the battery pack. The microcontroller also may communicate to the charger and can also monitor communication from the charger (in case of bi-directional communication). Typical communication through load modulation is described above.

(49) Another aspect of a wirelessly charged battery pack is the optional external/internal switch. A battery pack may receive power and be charged wirelessly or through the connectors of a battery

pack. For example when such a battery pack is used in a mobile phone, the user may wish to place the phone on a wireless charger or plug the device in to a wired charger for charging or charge the device as well as synchronize or upload and/or download information. In the second case, it may be important for the battery pack to recognize current incoming to the battery pack and to take some sort of action. This action may include notifying the user, shutting off the wired charger by a switch or simply shutting down the charger IC and sending a signal back through the microcontroller and modulating the current back to the charger that a wired charger is present (in case priority is to be given to the wired charger) or conversely to provide priority to the wireless charger and shut off wired charger access to battery when the wireless charger is charging the battery. At either case, a protocol for dealing with presence of two chargers simultaneously should be pre-established and implemented in hardware and firmware.

(50) As shown in FIG. 6, the wireless charging of battery occurs with current flowing into the battery through the battery contacts from the mobile device. Typically, such current is provided by an external DC supply to the mobile device (such as an AC/DC adaptor for a mobile phone) and the actual charging is handled by a charger IC chip or power management IC inside the mobile device that in addition to charging the battery, measures the battery's state of charge, health, verifies battery authenticity, and displays charge status through LEDs, display, etc. to a user. It may therefore be advantageous to include a current sense circuit at one of the battery pack contacts to measure and sense the direction of current flow into or out of the battery. In case the current is flowing in (i.e. battery being externally charged through wired charging through a mobile device), the micro-controller may take the actions described above and shut off wireless charging or conversely, provide priority to wireless charging and if it is present, not allow wired charging to occur as preferred by design.

(51) In accordance with an embodiment, the firmware in the receiver micro-controller is a key element in the operation of this battery pack. The micro-controller can measure voltages and currents, flags, and temperatures at appropriate locations for proper operation. In accordance with one embodiment, by way of example, the micro-controller can measure the value of $V_{sub.out}$ from the rectifier circuit and attempt to keep this constant throughout the charging cycle thereby providing a stable regulated DC supply to the charger IC chip. The microcontroller can send back the value of this voltage or error from a desired voltage (for example 5V) or simply a code for more or less power back to the charger in a binary or multi-level coding scheme through a load modulation or other scheme (for example RF communication as described earlier) back to the charger. The charger can then take action through adjustment of input voltage to the charger coil, adjustment of the frequency or duty cycle of the ac voltage applied to the charger coil to bring the $V_{sub.out}$ to within required voltage range. The micro-controller throughout the charging process, in addition, monitors the end of charge and/or other signals from charger and/or protection circuit and the current sense circuit (used to sense battery pack current direction and value) to take appropriate action. Li-ion batteries for example need to be charged below a certain temperature for safety reasons. It is therefore essential to monitor the cell, wireless power receiver coil or other temperature and take appropriate action such as terminate charging or lower charging current, etc. if a certain maximum temperature is exceeded.

(52) It is important to realize that during charging, as shown in FIG. 8, the battery cell voltage increases from 3 V or lower, to 4.2 V, as it is charged. The $V_{sub.out}$ of the wireless power receiver is input to a charger IC and if this $V_{sub.out}$ is kept constant (for example 5V), a large voltage drop (up to 2 V or more) can occur across this chip especially during Stage 1 where maximum current is applied. With charging currents of up to 1 A, this may translate to up to 2 Watts of wasted power/heat across this IC that may contribute to battery heating. It may be therefore preferable to implement a strategy whereby the $V_{sub.out}$ into the charger IC tracks the battery voltage thereby creating a smaller voltage drop and therefore loss across the charger IC. This can provide a significant improvement in performance since thermal performance of the battery pack is very

important.

(53) The communication between the receiver and charger needs to follow a pre-determined protocol, baud rate, modulation depth, etc. and a pre-determined method for hand-shake, establishment of communication, and signaling, etc. as well as optionally methods for providing closed loop control and regulation of power, voltage, etc. in the receiver.

(54) In accordance with an embodiment, a typical wireless power system operation can be as follows: As shown in FIG. 9, the charger periodically activates the charger coil driver and powers the charger coil with a drive signal of appropriate frequency. During this 'ping' process, if a receiver coil is placed on top or close to the charger coil, power is received through the receiver coil and the receiver circuit is energized. The receiver microcontroller is activated by the received power and begins to perform an initiation process whereby the receiver ID, its presence, power or voltage requirements, receiver or battery temperature or state of charge and/or other information is sent back to the charger. If this information is verified and found to be valid, then the charger proceeds to provide continuous power to the receiver. The receiver may alternately send an end of charge, over-temperature, battery full, or other messages that will be handled appropriately by the charger and actions performed. The length of the ping process should be planned to be of sufficient length for the receiver to power up its microcontroller and to respond back and for the response to be received and understood. The length of time between the pings is determined by the designer. If ping process is performed often, the stand-by power use of the charger is higher. Alternately, if the ping is done infrequently, the system will have a delay before the charger discovers a receiver nearby.

(55) Alternately, the ping operation can be initiated upon discovery of a nearby receiver by other means. This provides a very low stand-by power use by the charger and may be performed by including a magnet in the receiver and a magnet sensor in the charger or through optical, capacitive, weight or other methods for detection. Alternatively, the system can be designed to be always ON (i.e. the charger coil is powered at an appropriate drive frequency) and presence of the receiver coil brings the coil to resonance with the receiver coil and power transfer occurs. The receiver in this case may not even contain a microcontroller and act autonomously and simply have a regulator to provide regulated output power to a device, its skin or case, or battery.

(56) In accordance with an embodiment, the protocol for communication can be any of, e.g. common RZ, NRZ, Manchester code, etc. used for communication. An example of the communication process and regulation of power and/or other functions is shown in FIG. 10. As discussed above, the charger may periodically start and apply a ping voltage of pre-determined frequency and length to the charger coil (bottom figure in FIG. 10). The receiver is then activated and may begin to send back communication signals as shown in top of FIG. 10. The communication signal can include an optional preamble that is used to synchronize the detection circuit in the charger and prepare it for detection of communication. A communication containing a data packet may then follow, optionally followed by checksum and parity bits, etc. These processes are quite standard in communication systems and similar techniques can be followed. The actual data packet can include information such as an ID code for the receiver, received voltage, power, or current values, status of the battery, amount of power in the battery, battery or circuit temperature, end of charge or battery full signals, presence of external wired charger, or a number of the above. Also this packet may include the actual voltage, power, current, etc. value or the difference between the actual value and the desired value or some encoded value that will be useful for the charger to determine how best to regulate the output.

(57) Alternatively, the communication signal can be a pre-determined pattern that is repetitive and simply lets the charger know that a receiver is present and/or that the receiver is a valid device within the power range of the charger, etc. Any combination of systems can be designed to provide the required performance.

(58) In response to the receiver providing information regarding output power or voltage, etc. the

charger may modify voltage, frequency, duty cycle of the charger coil signal or a combination of the above. The charger can also use other techniques to modify the power out of the charger coil and to adjust the received power. Alternatively, the charger can simply continue to provide power to the receiver if an approved receiver is detected and continues to be present. The charger may also monitor the current into the charger coil and/or its temperature to ensure that no extra-ordinary fault conditions exist. One example of this type of fault may be if instead of a receiver, a metal object is placed on the charger.

(59) The charger can adjust a parameter to increase or decrease the power or voltage in the receiver and then wait for the receiver to provide further information before changing a parameter again or it can use more sophisticated Proportional Integral Derivative (PID) or other control mechanisms for closing the loop with the receiver and achieving output power control. Alternatively, as described above, the charger can provide a constant output power, and the receiver can regulate the power through a regulator or a charger IC or a combination of these to provide the required power to a device or battery.

(60) Various manufacturers may use different coding and also bit rates and protocol. The control process used by different manufacturers may also differ, further causing interoperability problems between various chargers and receivers. A source of interoperability differences may be the size, shape, and number of turns used for the power transfer coils. Furthermore, depending on the input voltage used, the design of a wireless power system may step up or down the voltage in the receiver depending on the voltage required by a device by having appropriate number of turns in the charger and receiver coils. However, a receiver from one manufacturer may then not be able to operate on another manufacturer charger due to these differences in designs employed. It is therefore extremely beneficial to provide a system that can operate with different receivers or chargers and can be universal.

(61) In accordance with an embodiment, to be able to detect and power/charge various receivers, the charger can be designed such that the initial Ping signal is at such a frequency range to initially be able to power and activate the receiver circuitry in any receiver during the ping process. After this initial power up of the receiver, the charger communication circuit should be able to detect and understand the communication signal from the receiver. Many microcontrollers are able to communicate in multiple formats and may have different input pins that can be configured differently to simultaneously receive the communication signal and synchronize and understand the communication at different baud rates and protocols. The charger firmware can then decide on what type of receiver is present and proceed to regulate or implement what is required (end of charge, shut-off, fault condition, etc.). Depending on the message received, then the charger can decide to change the charger driver voltage amplitude, frequency, or duty cycle or a combination of these to provide the appropriate regulated output.

(62) In accordance with an embodiment, the charger's behavior can also take into account the difference in the coil geometry, turns ratio, etc. For example, a charger and receiver pair from one or more manufacturers may require operation of the charger drive voltage at 150 kHz. However, if the same receiver is placed on a charger from another manufacturer or driven with different coil/input voltage combination, to achieve the same output power, the charger frequency may need to be 200 kHz. The charger program may detect the type of receiver placed on it and shift the frequency appropriately to achieve a baseline output power and continue regulating from there.

(63) As shown in FIG. 10, after the receiver sends back a communication signal back to the charger, in response to it, the charger adjusts its frequency and then awaits further information from the receiver. The receiver acknowledges the change and as shown in the second data packet in the receiver signal, has modified its state and communicates back to the charger. This closed loop continues during the charging process.

(64) For receivers that contain an onboard regulator for the output power, the input voltage to the regulator is not as critical since the regulator performs a smoothing function and keeps the output

voltage at the desired level with any load changes. It is however, important not to exceed the maximum rated input voltage of the regulator or to drop below a level required so that the output voltage could no longer be maintained at the required value. However, in general, inclusion of a regulator and/or a charger IC chip (for batteries) reduces the power/voltage regulation requirements at the expense of the additional size and cost of this component.

(65) While the system above describes a system where the communication is primarily through the coil, as described earlier, communication may be implemented through a separate coil, RF, optical system or a combination of the above. In such circumstances, a multi-protocol system can also be used to interoperate between systems with different communication and/or control protocols or even means of communication.

(66) Alternately, the receiver may be designed to accommodate different types of chargers. For example, once a receiver is awakened by a charger, it may try to detect the ping frequency used by the charger. This may be done by any number of phase locking or other techniques. Alternately, the receiver may send back a variety of trial communication signals during ping process to establish which type of device is performing the ping. Once the type of the charger is established, the receiver can proceed and communicate with the appropriate communication protocol and frequency with the charger.

(67) The multi-protocol approach described above is important for development of a universal system that can operate amongst multiple systems and provide user convenience.

(68) The description for the systems above may use discreet electronics components or some or all of the functions described above may be integrated into an Application Specific Integrated Circuit (ASIC) to achieve smaller footprint, better performance/noise, etc. and/or cost advantages. Such integration is common in the Electronics industry and can provide additional advantages here.

(69) Magnets for Use with Magnetically Sensitive Devices and Materials

(70) Magnetically sensitive devices, materials, or components are used in a variety of applications in industrial, consumer, credit, debit, Identification, or loyalty cards, computer, MP3 players, cameras, medical, satellite, marine, mining, transport, and military applications. Examples of magnetically sensitive components or sensors include traditional or electronic compasses, Hall sensors, magnetometers, disk drives, speakers, rotational or linear encoders, pneumatic sensors, electric motor position sensors, etc. These sensors monitor and/or measure slight amounts of magnetic field. For example, a traditional or electronic compass (consisting of magnetometer or Hall Effect sensors) responds to the small magnetic field of the earth to provide directional information to the user. Use of a magnet near such a device would alter its performance and reliability. However, there are instances where such a use would be beneficial. As an example, recently, there is interest in incorporation of electronic compasses in mobile devices such as phones, GPS, cameras, electronic tablets, and electronic compasses to provide the user a portable navigation capability. Simultaneously, these devices have often used magnets to secure the device in a holder, case, or holster or to attach the device to a surface such as a holder in a car. One example of use of magnets in mobile phones is in certain phones, such as Blackberry-type phones, where the presence of a device in its holster containing a small magnet is detected by a magnetic sensor in a phone and activates certain actions that may be selectable by the user on the phone. These actions can for example consist of turning the ringer on the phone off or switching to a vibrate mode.

(71) In cases such as the phone described above, if a magnetic compass is implemented in the phone, the presence of a magnet in a case can interfere with the operation of the compass and/or navigation capabilities of the device. Another example is the often used magnetic discs or clasps in cases or holders for phones or cameras to close a protective cover on a mobile device, phone, computer, GPS device, etc. In these and many other cases, it is desired to have an easy method of fastening two parts together magnetically while not affecting the operation of the device or system.

(72) FIG. 11 shows a Notebook-style portfolio case (left) and a mobile phone or camera pouch

(right), where magnets are used to secure a closing clasp or flap. Magnets have also been used to secure cases or portfolios to Notebook computers or the back of their screens. These devices often incorporate components such as disk drives or magnetically sensitive components such as compasses, etc. that may be affected by use of such magnets. In addition, the existing magnetic sensors in the device (as in the blackberry phone case discussed above) may be affected by such magnets.

(73) In addition, in many instances, it is desirable to hold or mount various devices securely by use of magnets. These can include having a convenient method for mounting of mobile phones, MP3 players, cameras, radar detectors, GPS units, compass, video screens, TVs, etc. in cars, boats, ships, trains, planes, helicopters, or other transport vehicles or work or home areas. Several commercially available mounts for such devices are shown in FIG. 12. In these instances, a magnetic or ferromagnetic base unit is coupled with a magnetic or ferromagnetic matching thin sticker or small sheet that can be attached or inserted inside a mobile device or its battery compartment or incorporated into a skin or case for the device such that the device will be attracted to the base and be held firmly during use or for storage. One or the other or both the holder or the mount and the other part incorporated into or on a device can be magnetic, to provide the necessary attractive force for this operation. Similarly, if the device is sensitive to magnetic fields, such a magnet can interfere with its operation.

(74) Another area of use of magnets is in design of handbags, bags, backpacks, wallets, money clasps, etc. where magnets are used as a convenient method of closing or fastening parts to close or shut parts together. Use of magnets in such instances where the user may place a magnetically sensitive device, phone, camera, MP3 player with disk drive, GPS unit, compass, or credit cards, etc. may cause problems. In particular, erasure of data in credit cards due to use of magnets in wallets or handbags can be a concern.

(75) More recently, magnets have been used to provide easy and safe connectivity between power or data cables and mobile devices or Notebook computers. As shown in FIG. 13 and described, for example in U.S. Pat. Nos. 7,311,526 and 7,645,143, a power plug for an electronic device or Notebook computer or deep fryer using a magnetic method for fastening and attachment of the power cable and its plug to the matching connector in the Notebook and a deep fryer. The magnet or ferromagnet material in the part of the plug surrounding the 5 connectors shown is attracted to the matching part in the Notebook and automatically aligns and connects the connectors in the 2 parts. The magnetic element on one or both of the plug and the device connector or receptacle can be a magnet to provide the necessary attractive force. The advantages of this type of connector is that in case a user accidentally trips over such a cable, it would easily pull the cable out of the Notebook computer or deep fryer without damage to either side and pulling the product off to the floor causing damage or injury. This is a considerable advantage over other types of connectors that are mated by force and insertion of one part into another and liable to break in case of such accidents or cause unnecessary damage or injury. However, similar to the situations described above, use of such types of magnets near devices that are sensitive to the magnetic field such as mobile phones with compasses or devices with magnetic sensors or hard drives near the connector is problematic and therefore similar connectors are not used in many devices that can take advantage of this technology.

(76) Another area of use of magnets is in the area of wireless power. With the proliferation of mobile devices in recent years, the area of powering and charging these devices has attracted more attention. The vast majority of the electronic devices in use today are powered and/or charged through conduction of electricity through wires from a power supply or charger to the device. While this method has proven to be efficient for most stationary devices, recently, there has been an interest in providing wireless methods for powering or charging several mobile devices, batteries, or electronics devices. The advantages include the ability to eliminate a power/charger cord and the possibility of implementing a universal charger/power supply that is able to charge/power multiple

devices one at a time or simultaneously. In addition, in many situations, eliminating the connectors for charging and/or power would improve device and/or battery reliability. The so called “wireless power” methods can also be generally divided into conductive and inductive methods. While the conductive methods use flow of current from a charger into the mobile devices and/or battery to provide power and therefore are not strictly speaking wireless, they offer geometries where a user can place a device on a pad or similar object and receive power through matching contacts on the back of a device and the pad without ‘plugging in’ the device. The inductive methods utilize coils or wires near the surface of a charger to create a magnetic field in the vicinity of the surface. A coil or wire in a receiver embedded into a device or battery that is in the vicinity of the surface can sense the magnetic field. Power from the charger can be transferred to the receiver without any wired connection through air or other media in between. The inductive method has several advantages over the conductive approach, such as:

(77) Connectors that are a major failure point in electronics are eliminated.

(78) Environmentally hermetic devices can be developed that are immune to moisture or liquids.

(79) The receiver can be built directly on the battery so the battery can be charged through the outside shell of the device by induction. This enables changing the battery of any existing product after-market with a similar sized and shaped battery to enable inductive charging.

(80) With a properly designed charger pad, the charging is independent of position and does not require placement of device in any particular location or orientation.

(81) Methods based on an array of connectors (e.g. U.S. Pat. No. 6,913,477 B2) or strips of power (e.g. www.pureenergy.com) in a pad that can power mobile devices conductively have been proposed. Sakamoto (H. Sakamoto and K. Harada in PESC'93 Record, pp168-174, Spain, (1992)) has also shown the possibility of recharging a device through a transformer coil with a core where the sections of the transformer can be separated. S. Hui, et al., in Electronics Letters, 34, pp. 1052-1054, (1998) and S. Tang, et al., Electronics Letters, 36, pp 943-944 (2000), describe the use of coreless printed circuit board transformers. Fernandez, et al., in Proc. APECOZ, 2002, pp. 339-345, have described the process of optimization of PCB coils for power transfer. The use of a resonance circuit is described in U.S. Publication No. 2009/0015075 and U.S. Publication No. 2009/0033564.

(82) As described herein, powering or charging of a mobile or electronic device or battery can be used interchangeably. Many mobile devices incorporate rechargeable batteries and require external DC power to charge these batteries for operation. However, in case of some devices such as a notebook, computer, etc., while the device is connected to DC power to charge its internal battery, the device can also be using the DC power to operate simultaneously. The ratio of power used for charging the internal rechargeable battery to operating the device depends on the degree to which the battery is discharged, the power necessary to operate the device, and what the device is doing at any given time. In the extreme, a laptop with its battery removed can only use the DC power to operate. In this case no charging occurs and 100% of the provided DC power is used to operate the device.

(83) In some of the applications described above, magnets can be used to provide alignment or a secure connection for an electrical contact. For example, in some implementations of the inductive charging technology, it may be desirable to provide alignment between the charger and receiver coils by aligning them through use of disk, ring, or other magnets attached to the two coils. When a receiver embedded in a device, battery, battery door, skin, or case is brought close to a charger surface, the corresponding magnets can attract and bring the coils to the necessary alignment for optimum power transfer. Several embodiments for implementing this, for example to provide higher insensitivity to placement of the receiver, better mechanical and smaller volume requirements, minimal impact on power transfer, etc., are described in U.S. patent applications “INDUCTIVE POWER SOURCE AND CHARGING SYSTEM”, application Ser. No. 11/669,113, filed Jan. 30, 2007 (subsequently published as U.S. Publication No. 20070182367, and issued as U.S. Pat. No. 7,952,322); “POWER SOURCE, CHARGING SYSTEM, AND INDUCTIVE

RECEIVER FOR MOBILE DEVICES”, application Ser. No. 11/757,067, filed Jun. 1, 2007 (subsequently published as U.S. Publication No. 20070279002, and issued as U.S. Pat. No. 7,948,208); “SYSTEM AND METHOD FOR INDUCTIVE CHARGING OF PORTABLE DEVICES”, application Ser. No. 12/116,876, filed May 7, 2008 (subsequently published as U.S. Publication No. 20090096413); and “SYSTEM AND METHODS FOR INDUCTIVE CHARGING, AND IMPROVEMENTS AND USES THEREOF”; application Ser. No. 12/769,586, filed Apr. 28, 2010 (subsequently published as U.S. Publication No. 20110050164), each of which applications are hereby incorporated by reference herein.

(84) FIG. 14 shows an Inductive wireless charger and/or power supply with multiple charging stations in accordance with an embodiment. The inductive receiver can be incorporated into a mobile device, its battery door, case or skin, a battery, etc. To align the coil in the charger and the coil in the receiver, magnets that attract the coils into alignment can be incorporated or on around the coils. Many types of magnets such as round discs, square, ring, oval, rectangular, arc, etc. can be used for alignment of coils. In FIG. 14, round disc (top) and ring (bottom) magnets are used for this alignment. One or many magnets can be used. Several different placements and shapes for magnets are shown in FIG. 15 by way of example. For example, a single disc or square, or other shaped magnet at the center of each coil can be used. In other implementations, 4 disc or square magnets placed in the corners of a square pattern can be used or other patterns. The patterns shown herein are shown by way of example. In accordance with other embodiments, other numbers and/or shapes of magnets or magnetization direction or strength can be used to achieve the desired alignment. It is possible to incorporate magnets with attracting magnetic orientation in the two parts to be aligned or alternatively, only one or one set of magnets and a ferromagnetic or magnetically attractable material used in the other part to achieve similar alignment results.

(85) The advantage of use of a single disc magnet in the center of a charger and one in the center of a receiver is that the receiver can rotate with respect to the charger and still maintain optimum alignment. With 4 magnets placed as shown in FIG. 15, the coils can be rotated 90, 180, or 270 degrees with respect to each other and still maintain alignment. Other shapes or number of magnets can be used and patterns in FIG. 15 are shown only as a way of example. The magnets can be magnetized with the magnet direction perpendicular to the face of the disk or magnet and by using magnet poles in the charger and receiver such that the pole is in the same direction in both, for example as south pole out of the page. When the two devices are close to each other, the magnets attract and align the coils. U.S. patent applications “INDUCTIVE POWER SOURCE AND CHARGING SYSTEM”, application Ser. No. 11/669,113, filed Jan. 30, 2007 (subsequently published as U.S. Publication No. 20070182367, and issued as U.S. Pat. No. 7,952,322); “POWER SOURCE, CHARGING SYSTEM, AND INDUCTIVE RECEIVER FOR MOBILE DEVICES”, application Ser. No. 11/757,067, filed Jun. 1, 2007 (subsequently published as U.S. Publication No. 20070279002, and issued as U.S. Pat. No. 7,948,208); “SYSTEM AND METHOD FOR INDUCTIVE CHARGING OF PORTABLE DEVICES”, application Ser. No. 12/116,876, filed May 7, 2008 (subsequently published as U.S. Publication No. 20090096413); and “SYSTEM AND METHODS FOR INDUCTIVE CHARGING, AND IMPROVEMENTS AND USES THEREOF”; application Ser. No. 12/769,586, filed Apr. 28, 2010 (subsequently published as U.S. Publication No. 20110050164), each of which applications are hereby incorporated by reference herein, each of which applications are hereby incorporated by reference herein, previously described improvements on the design of alignment magnets. For example, in FIG. 15 or FIG. 16, disc, square, rectangular, or ring magnets are used in the charger and the receiver with the magnets magnetized in the direction perpendicular to the flat surface. A gap in the ring magnet is incorporated to reduce potential eddy currents due to changing magnetic field of the wireless charger/power supply. Ring magnets have better performance for these applications due to the larger diameter of the magnet that can be used in this case (thereby providing a larger alignment target for the user), the ability to rotate one coil with respect to the other one at any angle and

maintain alignment, and the ability to reduce or eliminate any potential eddy currents through a cut in the ring as described above. In accordance with other embodiments, other shapes or combinations of shapes, such as square, rectangle, circle, oval, or triangle, etc. rings or other narrow wall, or others or combination of the above can be used depending on the particular needs of the intended application.

(86) In some situations, the charger/and or power supply is incorporated into a mobile device or part that includes a magnetically sensitive portion. For example, the charger can be incorporated into a notebook or laptop or computer with a disk drive, compass, or other magnetically sensitive parts. In these instances, incorporation of the magnet or magnets in the charger as well as the receiver can pose problems for the device incorporating the charger as well as for the device or part incorporating the receiver.

(87) In accordance with various embodiments, the coils described here can be manufactured with wires, Litz wire, Printed circuit board (PCB), stamped, formed, shaped, etc. metal or magnetic material. The spiral patterns shown here are for example only and the coils can be any shape or size or pattern that could generate a magnetic field.

(88) Similarly, the alignment can be achieved between a magnet or magnets incorporated into or around one of the coils and a part constructed of ferromagnetic or other magnetic material that can be attracted to the magnet for alignment. The magnet or the magnetically attracted part can be made from Nickel, Iron, Cobalt, gadolinium and dysprosium, steel, etc. or an alloy of these materials or ceramic, Alnico, Ticonal, Rare Earth magnets, flexible or injection molded or nano-crystalline magnets so that the magnets on the receiver attract and attach to the magnetic or ferromagnetic material on the other part. Examples of metal or magnetic material or ferromagnetic material that could form the opposite side are Nickel, Steel, cobalt, gadolinium and dysprosium, steel, etc. or an alloy of these material or ceramic, Alnico, Ticonal, Rare Earth magnetic material, flexible or injection molded or nano-crystalline materials or any other material that can be attracted to a magnet or an alloy containing such. Of course, either the receiver or charger can incorporate a magnet and the other part a material that is attracted to a magnet or vice versa or both can contain magnets with poles arranged such that they attract each other for alignment. The type of materials discussed above or combination thereof can be used in any of these cases. The magnets can be permanent magnets or electromagnets activated by application of an electrical current.

(89) Similarly, in conductive types of wireless or wire free charging or power, the connectors on a receiver in or on a device or skin, etc. are often magnetized to attract strips of metal or additional magnets on a pad to make a strong connection. For example, some companies produce a conductive type of so called “wireless” or “wire-free” charger. In some instances, connectors on the back of a mobile device incorporated into the device, its skin, or battery door, or an additional part attached to the back of the device contain a number of metallic contacts which make contact with metal strips on a pad. The metal strips are connected to a power supply rail with an applied voltage and upon contact with the receiver connectors and verification of the receiver, provide necessary voltage and/or current to the receiver. To enable a strong connection between the receiver and the pad metal strips or to enable the receiver and the device it is attached or incorporated in, to be placed at an angle or vertically, etc., the metal strips are made of a magnetic or ferromagnetic material such as Nickel, Iron, Cobalt, gadolinium and dysprosium, steel, etc. or an alloy so that the magnets on the receiver contact attract and attach to the strips. Enabling such an attractive contact is especially important when it is desired that the device not move during the charging process such as when the charger pad is used or incorporated into a car, airplane, ship, boat, etc. where motion is present. However, in instances where the mobile device contains a compass such as an electronic compass in certain phones, use of magnets in the receiver connectors interferes with such an operation. Therefore, the manufacturer has generally not incorporated magnetic connectors for such instances, which eliminates the benefits of the magnetic attachment.

(90) In these and many other applications, it may be desirable to benefit from the seemingly

contradictory use of magnets for their advantages in providing an attractive force for fastening, mounting, holding, or alignment, while at the same time it is desired to minimize or eliminate any effect on magnetically sensitive components in the charger or receiver or devices or parts nearby. This contradiction can be resolved by realizing that it is possible to create magnets with a net magnetic field that is zero or small in areas near or far from the magnet and at the same time that the part retains its magnetic or attractive properties at close distances and can provide attractive forces.

(91) To achieve small overall net magnetic field, it is important to realize that the magnetic field is a vector and fields from several magnets or parts or poles of the same magnet add to provide the total sum of the field at any location in space.

(92) Many magnets such as Rare Earth magnets are made using a sintering process whereby the basic material components such as Iron, Nickel, Cobalt, and/or Rare Earth material are refined and then combined in the desired composition and melted in a furnace to produce starting ingots for a magnet. The ingots are then ground and the resulting particles are placed in a jig or mold with the desired shape and dimensions and pressed into shape while an external magnetic field is applied to orient the particles. By applying the appropriate magnetic field in the desired direction, in plane, out of plane, radial, or multi-pole poling of the magnet can be achieved. For example, multi-pole magnets are created by pulse magnetization. To create a linear period multi-pole magnet, a magnetizing fixture with a back and forth copper wire arrangement is used. Application of a short current pulse from a capacitor through the fixture produces a magnetic field strong enough to magnetize material in the vicinity of the wire pattern. By controlling the shape and size of the induced magnetic field various magnet types can be created. The resulting part is then treated in a sintering furnace to compact the material before further testing of the parameters and coating of the final magnet to avoid corrosion. As an example, multi-pole magnets with periodicity of 1-2 mm in substrates of 2 mm thick or less have been studied for micro-actuator applications (J. Töpfer, and V. Christoph, "Multi-pole Magnetization of NdFeB Sintered Magnets and Thick Films for Magnetic Micro-Actuators", *Sensors and Actuators, A* 113 (2004) 257-263 AND J. Töpfer, B. Pawlowski, H. Beer, K. Plötner, P. Hofmann, M. Herfurth, "Multi-pole magnetization of NdFeB magnets for magnetic micro-actuators and its characterization with a magnetic field mapping device, *J. Magn. Magn. Mater.* 270 (2004) 124-129).

(93) Töpfer, et al. manufactured NdFeB square magnets of 50×50×1 mm.^{sup.3} dimension magnetized axially perpendicular to the square surface of the part and characterized it. FIG. **16** shows Measured z-component (along the axial direction of magnetization) of the magnetic flux density of this magnet measured by moving a Hall Sensor along the middle of one edge of the square to the opposite edge of the square 250 micrometers above the surface of the magnet as shown in the inset. The results show that in such a magnet, the field peaks at the edges and in the center, a strong demagnetization field exists that almost reduces the magnetic flux to zero at this center, thereby not providing much attractive or retention force for such thin magnets.

(94) In FIG. **17**, the same researchers compare the performance of a 50×50×1 mm.^{sup.3} magnet with one of 10×10×1 mm.^{sup.3} dimension magnetized axially perpendicular to the square surface of the part. The smaller magnet retains its magnetic flux to a greater degree at its center and has higher peaks at the edges. Also note that the peak of the magnetic flux is higher for this magnet.

(95) To further retain high flux density in a magnet, the same shape part can be periodically poled in a multi-pole pattern as shown in FIG. **18**. Here, the 10×10×1 mm.^{sup.3} magnet is magnetized periodically with a periodicity of 2 mm as shown on the top FIG. **18**. The bottom figure shows the measured magnetic flux density. It can be seen that flux density follows the poling pattern but in addition, comparing the magnitude of the flux density, it can be seen that the peak values are about twice the peak value of the flux density in a uniformly magnetized magnet. In addition, the magnetic flux does not show any sign of demagnetization and reduction of the peak values at the center of the magnet that is seen in FIGS. **16** and **17**. Overall, multi-pole magnetization can provide

a method for achieving higher and more uniform magnetic flux in a magnet. These characteristics are desirable for applications described here where retention and alignment of parts are required.

(96) An important aspect of the performance of the multi-pole magnets described here is the performance of these magnets away from the surface of the magnets. FIG. **19** shows the drop off of maximum flux density value for a $10 \times 10 \times 1$ mm.sup.3 magnet magnetized periodically with a periodicity of 1 and 2 mm as shown on the top as a function of distance between the probe and the top of the magnet. It can be seen that the flux density drops off very quickly and reaches small values for over 1 mm. This is a result of the geometry shown on the top of the figure. With multiple poles present, as the distance between the probe and the magnet increases, the probe measures the sum of the flux density from the multiple poles present and this value approaches zero quickly away from the surface. At the same time, near the surface, the flux density is larger for the multi-pole magnet as compared to a single pole magnet, and increases as the pole periodicity increases (up to a limit given the physical dimensions of the magnet, its thickness, etc.). It is important to recall that the peak for a uniformly magnetized magnet of same dimension was only around 0.13 T (<1/3 of the 1 mm periodically poled similarly sized magnet value) as shown in FIGS. **18** and **19**. At the same time, as discussed above, the uniformly magnetized magnet also showed a very significant reduction of the flux density at its center which is not present for the multi-pole magnet.

(97) In summary, the results above demonstrate that properly designed multi-pole magnets can provide significantly higher and more uniform flux density near their surface while at the same time providing much lower flux densities away from the surface.

(98) These characteristics can be used to provide the combination of characteristics that are useful for mounting, holding, attachment, and alignment purposes for the applications discussed earlier. By using multi-pole magnets higher retention and alignment force can be provided, while reducing the effect of any stray fields on nearby magnetically sensitive components, parts, or materials.

(99) FIG. **20** shows several magnet types that are magnetized perpendicular to the magnet surface (axially), in accordance with various embodiments. For example, FIG. **20** shows (a) rectangular magnet magnetized in a checkerboard pattern, (b) square magnet magnetized in a checkerboard pattern, (c) rectangular magnet magnetized in a single direction multi-pole pattern, (d) square magnet magnetized in a single direction multi-pole pattern, (e) disc magnet magnetized into 4 sections, (f) disc magnet magnetized into 8 sections, (g) ring magnet magnetized into 8 sections, and (h) disc magnet magnetized into concentric circular sections. These patterns are shown by way of illustration, and it is obvious that many types of magnets and shapes can be devised for various applications with regular or irregular shapes that have multi-pole magnetic patterns.

(100) For applications in securing or mounting of parts to another part, a multi-pole magnet similar to magnets in FIG. **20** or another appropriate shape and size and number of poles can be devised for the device to be mounted or the mount and combined with a matching magnet or ferromagnet or other magnetically attractable material on the opposite part (device or mount) to provide attraction between the two parts. Since each magnet includes a number of poles, this approach allows both for central alignment between the two parts (i.e. their respective magnets or magnetically attractable material are centered with respect to one another); and stepped or rotational alignment between the two parts (i.e. their respective magnets or magnetically attractable material can be center-aligned with respect to one another, and then rotated around those centers in steps corresponding to the number of poles, wherein at each step the full magnetic attraction is provided). This allows for novel uses of such magnets, for example to allow parts to be attached to one another in a variety or particular number of relative orientations.

(101) In accordance with an embodiment, in applications such as shown in FIG. **11-15**, the appropriately designed magnet can be used instead of the uniformly magnetized magnets of earlier design, to provide stronger or similar attractive force while producing minimal or zero magnetic field away from the magnet not to disturb other magnetically sensitive parts or devices.

(102) As an example, in accordance with various embodiments, ring or arc multi-pole magnets such

as those shown in FIG. 21 can be used with the coil to provide alignment. It will be evident that improvements such as cuts or discontinuities, etc. for reduction of eddy currents can be implemented as in singly poled magnets described for example in U.S. patent applications "INDUCTIVE POWER SOURCE AND CHARGING SYSTEM", application Ser. No. 11/669,113, filed Jan. 30, 2007 (subsequently published as U.S. Publication No. 20070182367, and issued as U.S. Pat. No. 7,952,322); "POWER SOURCE, CHARGING SYSTEM, AND INDUCTIVE RECEIVER FOR MOBILE DEVICES", application Ser. No. 11/757,067, filed Jun. 1, 2007 (subsequently published as U.S. Publication No. 20070279002, and issued as U.S. Pat. No. 7,948,208); "SYSTEM AND METHOD FOR INDUCTIVE CHARGING OF PORTABLE DEVICES", application Ser. No. 12/116,876, filed May 7, 2008 (subsequently published as U.S. Publication No. 20090096413); and "SYSTEM AND METHODS FOR INDUCTIVE CHARGING, AND IMPROVEMENTS AND USES THEREOF"; application Ser. No. 12/769,586, filed Apr. 28, 2010 (subsequently published as U.S. Publication No. 20110050164), each of which applications are hereby incorporated by reference herein. For example, the ring magnet in FIG. 22 shows an implementation of such a discontinuity at the bottom of the figure.

(103) While most of the description below is based on the inductive method of power transfer, the embodiments described here can be implemented with either the inductive method or the conductive method or the magnetic resonance method, optical, or other methods for power transfer some of which have been described above. Inductive methods of power transfer are described above as an example of the more general wireless power transfer.

(104) Furthermore, the type of magnets discussed above may be used with magnetic shielding material commonly in use for reduction of AC or DC magnetic field such as mumetal, etc. available from Magnetic Shield Corporation or material such as thin flexible sheets available from Maruwa or nano materials such as Finemet from Hitachi Corp or ferromagnetic or alloys of ferromagnetic materials such as iron, nickel and cobalt. For example, in the case of the inductive charger or receiver described above, the area behind a coil can be covered by a magnetic shield material and a square, rectangle, ring or arc of multi-pole magnet can be attached around and/or on such a shield and be used for attraction and alignment of the charger and receiver coil to each other. FIG. 22 shows such an arrangement where multi-pole magnets (multi-pole ring (left) and arc (right) magnet on or around an inductive coil) and magnetic shielding material are used behind a coil. Here, the magnetic shield layer or material shields behind the coil provides shielding from the alternating magnetic field of the coil. An optional cut/discontinuity in the ring (shown at the bottom of the ring magnet on the left) prevents or reduces eddy currents during operation of the inductive coil.

(105) In addition, heat transfer layers can be incorporated to spread the heat generated. Such layers need to be designed not to interfere with the operation of the coils. Since alternating magnetic fields are generated and detected in an inductive system, use of a metal layer behind the coil would produce eddy currents and loss. One method for providing thermal conductivity with metal layers is where a metal layer with discontinuous portions is placed behind and/or around the coil. In this case, the metal layer can comprise rectangular slices that can conduct heat away from the center of a coil while, due to discontinuity between the slices, the electrons can not flow in a circular motion due to the alternating magnetic field. The pattern described here has a number of triangular slices but any other pattern which can provide heat transport but does not allow carriers to circulate in a rotational pattern due to the alternating magnetic field can be implemented.

(106) Alternatively, multi-pole magnets can be manufactured by way of taking a single poled magnet, cutting it into appropriate sections, and reassembling the pieces and attaching them together with an adhesive, glue, or other bonding agent or other material; or alternatively, a holder, etc. or clamp or screws or external force or other methods, so that the multi-pole geometry is achieved. For example, a single poled axially poled (out of plane of ring) ring can be cut into 4, 8, 16, or another number of even or odd sections, and half of the sections turned over and reassembled to provide a multi-pole magnet. To aid in assembly of such a magnet, it may be necessary to attach

or place the parts on to another solid continuous piece. This piece may be magnetic, ferromagnetic, or non-magnetic itself. For example, in the ring magnet example above, the pieces of the ring magnet can be attached and reassembled in a multi-pole geometry on a stainless steel, iron, Nickel, plastic, or copper, etc. ring to aid in assembly and to hold the sections together. The properties of the backing material, its thickness, etc. can also be optimized to provide necessary performance. For example, use of a ferromagnetic material as backing can further provide a path for the magnetic flux in that section and provide further tighter coupling between sections and reduction of magnetic field away from the ring. It may also be desirable to sandwich the magnet on both sides with similar or dissimilar backing material or layers, or use multiple backing layers to further engineer symmetric or asymmetric properties on the two sides of the multi-pole magnet.

(107) FIG. 23 shows a multi-pole ring magnet with radially magnetized sections. In use of the magnet for inductive charging applications, a cut or break in the circle or arc magnets as described earlier can be used.

(108) While in the above description, emphasis has been given to affixing electronic parts, batteries, electric parts, etc to other parts or components or cases, holders, etc., the processes, systems, and methods described above can be similarly used to permanently or temporarily fix, attach, align, or establish relation between any two or more parts of the same or different items, products, areas, etc., including those not directly related to electronics. Examples include in lighting, furniture, automotive, mechanical instruments or machines, electronics, electrical systems and components, batteries, cases, purses, clothing, footwear, or any other number of applications. Other examples can be developed in accordance with other applications.

(109) Some aspects of the present invention can be conveniently implemented using a conventional general purpose or a specialized digital computer, microprocessor, or electronic circuitry programmed according to the teachings of the present disclosure. Appropriate software coding can readily be prepared by skilled programmers and circuit designers based on the teachings of the present disclosure, as will be apparent to those skilled in the art.

(110) In some embodiments, the present invention includes a computer program product which is a storage medium (media) having instructions stored thereon/in which can be used to program a computer to perform any of the processes of the present invention. The storage medium can include, but is not limited to, any type of disk including floppy disks, optical discs, DVD, CD-ROMs, microdrive, and magneto-optical disks, ROMs, RAMs, EPROMs, EEPROMs, DRAMs, VRAMs, flash memory devices, magnetic or optical cards, nanosystems (including molecular memory ICs), or any type of media or device suitable for storing instructions and/or data.

(111) The foregoing description of the present invention has been provided for the purposes of illustration and description. It is not intended to be exhaustive or to limit the invention to the precise forms disclosed. Many modifications and variations will be apparent to the practitioner skilled in the art. The embodiments were chosen and described in order to best explain the principles of the invention and its practical application, thereby enabling others skilled in the art to understand the invention for various embodiments and with various modifications that are suited to the particular use contemplated. It is intended that the scope of the invention be defined by the following claims and their equivalence.

Claims

1. An inductive charger for inductive charging a battery in an electronic device having a substantially planar receiver coil, the inductive charger comprising: a substantially planar inductive charger coil comprising Litz wire wound in a substantially spiral shape for generating an alternating magnetic field substantially perpendicular to the plane of the inductive charger coil to transfer inductive power to the receiver coil in the electronic device for charging the battery in the electronic device; a magnetic structure configured to generate a magnetic field that creates a

magnetic attachment between the inductive charger and the electronic device and to align the inductive charger coil with the receiver coil of the electronic device for inductive power transfer for charging the battery in the electronic device, the magnetic structure comprising two or more discontinuous arc-shaped permanent magnet sections that define a substantially flat first surface and a substantially flat second surface opposite the first surface, wherein each magnetic section comprises at least two magnetic poles of opposite polarity located at each of the first and second surfaces of each magnetic section such that each magnetic section includes at least two pairs of opposing magnetic poles oriented to cause magnetization in two opposing directions that are each perpendicular to the first and second surfaces, wherein the magnetic sections are assembled to form a full or partial ring shape and the magnetic structure is positioned around an outer perimeter of the inductive charger coil and is substantially concentric with the inductive charger coil, and wherein the magnetic structure is configured to create a magnetic field with flux densities having substantially similar magnitudes relative to the first and second surfaces as a function of distance from the first and second surfaces, respectively, along an axis that runs perpendicular to the first and second surfaces; and a magnetic shield layer comprising a nano-crystalline material positioned parallel to the plane of the inductive charger coil on a side of the inductive charger coil that is opposite the electronic device during inductive power transfer, wherein the magnetic shield layer is positioned to shield a portion of the inductive charger from the alternating magnetic field while transferring the inductive power; wherein the magnetic structure is configured such that: the magnetic field generated by the magnetic structure does not impair operation of the magnetic shield layer during the inductive power transfer, and the electronic device can be rotated across a continuous range of rotational angles with respect to the inductive charger while keeping the alignment between the inductive charger coil and the inductive receiver coil during inductive power transfer for charging the battery in the electronic device.

2. The inductive charger of claim 1, wherein the magnetic sections in the magnetic structure are poled with the same orientation.

3. The inductive charger of claim 1, further comprising a magnetic sensor configured to detect the presence of an additional magnetic field of a nearby compatible magnetic structure in the electronic device to initiate inductive charging.

4. The inductive charger of claim 1, wherein the full or partial ring shape of the magnetic structure includes at least one electrically non-conductive gap.

5. The inductive charger of claim 1, further comprising an additional magnetic structure that defines a substantially flat third surface and a substantially flat fourth surface, wherein the additional magnetic structure is magnetized in a direction perpendicular to the third and fourth surfaces of the additional magnetic structure, wherein the third and fourth surfaces of the additional magnetic structure each include at least two magnetic poles of opposite polarity, wherein the additional magnetic structure is configured to align the electronic device in a predetermined rotational orientation relative to the inductive charger, and wherein the additional magnetic structure is configured to not impair operation of an electronic compass in the electronic device or the inductive power transfer.

6. An electronic device configured for receiving inductive power from an inductive charger, the electronic device comprising: a rechargeable battery to operate the electronic device; a substantially spiral shaped and substantially planar inductive charging receiver coil for receiving inductive power to charge the rechargeable battery, wherein the inductive charging receiver coil is configured to receive an alternating magnetic field substantially perpendicular to the plane of the inductive charging receiver coil from a substantially planar charger coil in the inductive charger for receiving inductive power to charge the rechargeable battery; a magnetic structure configured to generate a magnetic field that creates a magnetic attachment between the electronic device and the inductive charger and to align the inductive charging receiver coil of the electronic device with the charger coil in the inductive charger for receiving inductive power to charge the rechargeable battery of the

electronic device, wherein the magnetic structure comprises two or more discontinuous arc-shaped permanent magnet sections that define a substantially flat first surface and a substantially flat second surface opposite the first surface, wherein the magnetic sections are assembled to form a full or partial ring shape and the magnetic structure is positioned around an outer perimeter of the inductive charging receiver coil and is substantially concentric with the inductive charging receiver coil, wherein each magnetic section is magnetized with multiple poles radially such that a first pole of the multiple poles of each magnetic section is located, relative to a second pole of the multiple poles, closer to an inner radius of the full or partial ring shape, and wherein the second pole of the multiple poles of each magnetic section is located, relative to the first pole, closer to an outer radius of the full or partial ring shape to form a magnetic field for each magnetic section that is substantially parallel to the substantially planar surface of the inductive charging receiver coil, wherein all the magnetic sections of the magnetic structure are poled with the same orientation, and wherein the magnetic structure is configured to create a magnetic field with flux densities having substantially similar magnitudes relative to the first and second surfaces as a function of distance from the first and second surfaces, respectively, along an axis that runs perpendicular to the first and second surfaces; and a magnetic shield layer comprising a nano-crystalline material positioned parallel to the plane of the inductive charging receiver coil on a side of the inductive charging receiver coil that is opposite the inductive charger while receiving inductive power, wherein the magnetic shield layer is positioned to shield the electronic device from the alternating magnetic field while receiving the inductive power; wherein the magnetic structure is configured such that: the magnetic field generated by the magnetic structure does not impair operation of the magnetic shield layer while receiving the inductive power, and the electronic device can be rotated across a continuous range of rotational angles with respect to the inductive charger while keeping the alignment between the inductive charging receiver coil and the charger coil when receiving inductive power to charge the rechargeable battery.

7. The electronic device of claim 6, wherein the full or partial ring shape of the magnetic structure includes at least one electrically non-conductive gap.

8. The electronic device of claim 6, further comprising a wired charging connector and circuitry for receiving power to charge the rechargeable battery from a wired charger, wherein the electronic device is configured to detect when power is available through both the wired charging connector and the inductive charging receiver coil, and wherein the electronic device is further configured to switch between receiving power through the wired charging connector and receiving power through the inductive charging receiver coil based on a priority pre-established by the electronic device.

9. The electronic device of claim 6, further comprising: an electronic compass; and an additional magnetic structure that defines a substantially flat third surface and a substantially flat fourth surface, wherein the additional magnetic structure is magnetized in a direction perpendicular to the third and fourth surfaces of the additional magnetic structure, wherein the third and fourth surfaces of the additional magnetic structure each include at least two magnetic poles of opposite polarity, wherein the additional magnetic structure is configured to align the electronic device in a predetermined rotational orientation relative to the inductive charger, and wherein the additional magnetic structure is configured to not impair operation of an electronic compass in the electronic device or the receipt of inductive power.

10. The electronic device of claim 6, further comprising a heat transfer layer approximately parallel to the magnetic shield layer such that the magnetic shield layer is between the heat transfer layer and the inductive charging receiver coil.

11. A stand-alone accessory device for a separate electronic device having a magnetic shield layer and a substantially planar inductive charging coil for inductive power transfer, the accessory device comprising: a substantially flat magnetic structure configured to generate a magnetic field that creates a magnetic attachment to the electronic device and to align the accessory device with the

electronic device, wherein the magnetic structure comprises one or more arc-shaped permanent magnet sections that define a substantially flat first surface and a substantially flat second surface opposite the first surface, wherein each magnetic section includes at least two magnetic poles of opposing polarity located at each of the first and second surfaces of each magnetic section such that each magnetic section includes at least two pairs of opposing magnetic poles oriented to cause magnetization in two opposing directions that are each perpendicular to the first and second surfaces, wherein the magnetic sections are assembled to form a full or partial ring shape and the magnetic structure is configured to be positioned, when magnetically attached to the electronic device, around an outer perimeter of the inductive charging coil and to be substantially concentric with the inductive charging coil, wherein the magnetic field generated by the magnetic structure is configured with flux densities having substantially similar magnitudes relative to the first and second surfaces as a function of distance from the first and second surfaces, respectively, along an axis that runs perpendicular to the first and second surfaces, and wherein the magnetic structure is configured such that the magnetic structure does not impair operation of the magnetic shield layer and the electronic device.

12. The accessory device of claim 11, wherein all the magnetic sections of the magnetic structure are poled with the same orientation.

13. The accessory device of claim 11, wherein the full or partial ring shape of the magnetic structure includes at least one electrically non-conductive gap.

14. The accessory device of claim 11, wherein the electronic device is a mobile device and configured to receive inductive power transfer.

15. The accessory device of claim 11, wherein the electronic device is an inductive charger and configured to transmit inductive power transfer.

16. The accessory device of claim 11, further comprising an additional magnetic structure that defines a substantially flat third surface and a substantially flat fourth surface, wherein the additional magnetic structure is magnetized in a direction perpendicular to the third and fourth surfaces of the additional magnetic structure, wherein the third and fourth surfaces of the additional magnetic structure each include at least two magnetic poles of opposite polarity, and wherein the additional magnetic structure is configured to not impair operation of an electronic compass in the electronic device or the inductive power transfer.

17. The accessory device of claim 16, wherein the additional magnetic structure is configured to align the electronic device in a predetermined rotational orientation relative to a second electronic device.

18. The accessory device of claim 11 wherein the magnetic structure is flexible.

19. The accessory device of claim 11, wherein the accessory device is a protective case or pouch for the electronic device.

20. The accessory device of claim 11, wherein the accessory device is a mounting apparatus configured to mount the electronic device inside a vehicle.

21. The accessory device of claim 20, further comprising an inductive charger for charging the electronic device while it is mounted.

22. The accessory device of claim 11, wherein the accessory device is a wallet or money clasp configured to contain at least one debit or credit card, and wherein the magnetic structure of the accessory device does not interfere with a magnetic strip of the at least one contained debit or credit card.

23. The accessory device of claim 11, wherein the accessory device is a magnetic sticker configured to attach to the electronic device to enable attachment and alignment of an additional device to the electronic device.

24. A protective case for an electronic device having a battery, a nano-crystalline magnetic shield layer, and a substantially planar inductive charging receiver coil for receiving inductive power from an inductive charger comprising a substantially planar charger coil to charge the battery, the

protective case comprising: a substantially flat magnetic structure configured to generate a magnetic field, the magnetic structure comprising one or more arc-shaped permanent magnet sections that define a substantially flat first surface and a substantially flat second surface opposite the first surface, wherein the magnetic sections are assembled to form a full or partial ring shape, wherein the magnetic structure is configured to be positioned around an outer perimeter of the inductive charging receiver coil of the electronic device and to be substantially concentric with the inductive charging receiver coil when the electronic device is placed in the protective case, wherein each permanent magnet section includes at least two magnetic poles of opposing polarity located at each of the first and second surfaces of each permanent magnet section such that each permanent magnet section includes at least two pairs of opposing magnetic poles oriented to cause magnetization in two opposing directions that are each perpendicular to the first and second surfaces, wherein the magnetic structure is configured to create a magnetic field with flux densities having substantially similar magnitudes relative to the first and second surfaces as a function of distance from the first and second surfaces, respectively, along an axis that runs perpendicular to the first and second surfaces, wherein the magnetic structure is configured such that the electronic device, when placed in the protective case, can be rotated across a continuous range of rotational angles with respect to the inductive charger while keeping the alignment between the inductive charger coil and the inductive receiver coil while receiving inductive power from the inductive charger for inductive charging the battery in the electronic device, and wherein the magnetic structure is configured such that the magnetic field generated by the magnetic structure does not impair operation of the magnetic shield layer and the inductive charging receiver coil for receiving inductive power to charge the battery in the electronic device.

25. The protective case of claim 24, wherein all magnetic sections of the magnetic structure are poled with the same orientation.

26. The protective case of claim 24, wherein the full or partial ring shape of the magnetic structure includes at least one electrically non-conductive gap.

27. The protective case of claim 24, further comprising an additional magnetic structure that defines a substantially flat third surface and a substantially flat fourth surface, wherein the additional magnetic structure is magnetized in a direction perpendicular to the third and fourth surfaces of the additional magnetic structure, wherein the third and fourth surfaces of the additional magnetic structure each include at least two magnetic poles of opposite polarity, and wherein the additional magnetic structure is configured to not impair operation of an electronic compass in the electronic device or the receipt of inductive power.

28. The protective case of claim 27, wherein the additional magnetic structure is configured to align the electronic device in a predetermined rotational orientation relative to the inductive charger.

29. The protective case of claim 24, wherein the magnetic structure is flexible.

30. The protective case of claim 24, wherein the protective case is a wallet or money clasp configured to contain at least one debit or credit card, and wherein the magnetic structure of the protective case does not interfere with a magnetic strip of the at least one contained debit or credit card.
