

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287667

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

CHIU; Yen-Jui et al.

FORMATION OF TRANSISTOR GATES

Abstract

A method includes following steps. A first gate dielectric layer is deposited over a first semiconductor channel and a second semiconductor channel. A second gate dielectric layer is deposited over the first gate dielectric layer. A layer is formed over the second gate dielectric layer using atomic layer deposition (ALD) cycles each comprising sequentially performing a first pulse step for a first pulse time, a first purge step for a first purge time, a second pulse step for a second pulse time, and a second purge step for a second purge time. A ratio of the first purge time to the first pulse time is greater than a ratio of the second purge time to the second pulse time. The layer is patterned to expose a portion of the second gate dielectric layer. The exposed portion of the second gate dielectric layer is etched.

Inventors: CHIU; Yen-Jui (Hsinchu, TW), CHUANG; Yao-Teng (Hsinchu, TW), LIN; Kuei-Lun (Keelung City, TW)

Applicant: TAIWAN SEMICONDUCTOR MANUFACTURING COMPANY, LTD.
(Hsinchu, TW)

Family ID: 82136168

Assignee: TAIWAN SEMICONDUCTOR MANUFACTURING COMPANY, LTD.
(Hsinchu, TW)

Appl. No.: 19/216886

Filed: May 23, 2025

Related U.S. Application Data

parent US continuation 18403523 20240103 parent-grant-document US 12336251 child US 19216886

parent US continuation 17340037 20210606 parent-grant-document US 11901436 child US 18403523

us-provisional-application US 63157499 20210305

Publication Classification

Int. Cl.: **H10D64/01** (20250101); **H10D30/67** (20250101); **H10D86/01** (20250101)

U.S. Cl.:

CPC **H10D64/017** (20250101); **H10D64/01** (20250101); **H10D86/0221** (20250101);
H10D86/0231 (20250101); H10D30/6735 (20250101)

Background/Summary

PRIORITY CLAIM AND CROSS-REFERENCE [0001] This application is a continuation of U.S. patent application Ser. No. 18/403,523, filed Jan. 3, 2024, which is a continuation of U.S. patent application Ser. No. 17/340,037, filed Jun. 6, 2021, now U.S. Pat. No. 11,901,436, issued on Feb. 13, 2024, which claims the benefit of U.S. Provisional Application No. 63/157,499, filed on Mar. 5, 2021, all of which are herein incorporated by reference in their entirety.

BACKGROUND

[0002] Semiconductor devices are used in a variety of electronic applications, such as, for example, personal computers, cell phones, digital cameras, and other electronic equipment. Semiconductor devices are typically fabricated by sequentially depositing insulating or dielectric layers, conductive layers, and semiconductor layers of material over a semiconductor substrate, and patterning the various material layers using lithography to form circuit components and elements thereon.

[0003] The semiconductor industry continues to improve the integration density of various electronic components (e.g., transistors, diodes, resistors, capacitors, etc.) by continual reductions in minimum feature size, which allow more components to be integrated into a given area.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0004] Aspects of the present disclosure are best understood from the following detailed description when read with the accompanying figures. It is noted that, in accordance with the standard practice in the industry, various features are not drawn to scale. In fact, the dimensions of the various features may be arbitrarily increased or reduced for clarity of discussion.

[0005] FIG. 1 illustrates an example of gate-all-around field-effect transistors (GAA-FETs) in a three-dimensional view, in accordance with some embodiments.

[0006] FIGS. 2-5, 6A, 13A, 14A, 15A, 16A, 17A, 18A, 19A, 19C, 19E, 20A, 20C, 21A, 22A, 23A, and 24A are cross-sectional views at intermediate fabrication stages, illustrating reference cross-section A-A' illustrated in FIG. 1 that extends through a gate region along a longitudinal axis of the gate region.

[0007] FIGS. 6B, 7B, 8B, 9B, 10B, 11B, 11C, 12B, 12D, 13B, 14B, 15B, 16B, 17B, 18B, 19B, 19D, 20B, 20D, 21B, 22B, 23B, and 24B are cross-sectional views at intermediate fabrication stages, illustrating reference cross-section B-B' illustrated in FIG. 1 that extends through a fin along a longitudinal axis of the fin.

[0008] FIGS. 7A, 8A, 9A, 10A, 11A, 12A, 12C, and 13C are cross-sectional views at intermediate fabrication stages, illustrating reference cross-section C-C' illustrated in FIG. 1 that extends through source/drain regions along the longitudinal direction of the gate region.

[0009] FIG. 25 illustrates an example atomic layer deposition (ALD) tool that may be used to form a hard mask layer during fabricating gate stacks of GAA-FETs, in accordance with some embodiments of the present disclosure.

[0010] FIG. 26 illustrates an ALD process that may be used to form a hard mask layer during fabricating gate stacks of GAA-FETs, in accordance with some embodiments of the present disclosure.

DETAILED DESCRIPTION

[0011] The following disclosure provides many different embodiments, or examples, for implementing different features of the provided subject matter. Specific examples of components and arrangements are described below to simplify the present disclosure. These are, of course, merely examples and are not intended to be limiting. For example, the formation of a first feature over or on a second feature in the description that follows may include embodiments in which the first and second features are formed in direct contact, and may also include embodiments in which additional features may be formed between the first and second features, such that the first and second features may not be in direct contact. In addition, the present disclosure may repeat reference numerals and/or letters in the various examples. This repetition is for the purpose of simplicity and clarity and does not in itself dictate a relationship between the various embodiments and/or configurations discussed.

[0012] Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 230 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly. As used herein, “around,” “about,” “approximately,” or “substantially” may generally mean within 20 percent, or within 10 percent, or within 5 percent of a given value or range. Numerical quantities given herein are approximate, meaning that the term “around,” “about,” “approximately,” or “substantially” can be inferred if not expressly stated.

[0013] The present disclosure is generally related to integrated circuit (IC) structures and methods of forming the same, and more particularly to fabricating gate-all-around (GAA) transistors having different high-k gate dielectric compositions. It is also noted that the present disclosure presents embodiments in the form of multi-gate transistors. Multi-gate transistors include those transistors whose gate structures are formed on at least two-sides of a channel region. These multi-gate devices may include a p-type metal-oxide-semiconductor device or an n-type metal-oxide-semiconductor device. Specific examples may be presented and referred to herein as FinFET, on account of their fin-like structure. Also presented herein are embodiments of a type of multi-gate transistor referred to as a gate-all-around (GAA) device. A GAA device includes any device that has its gate structure, or portion thereof, formed on 4-sides of a channel region (e.g., surrounding a portion of a channel region). Devices presented herein also include embodiments that have channel regions disposed in nanosheet channel(s), nanowire channel(s), and/or other suitable channel configuration. Presented herein are embodiments of devices that may have one or more channel regions (e.g., nanosheets) associated with a single, contiguous gate structure. However, one of ordinary skill would recognize that the teaching can apply to a single channel (e.g., single nanosheet) or any number of channels. One of ordinary skill may recognize other examples of semiconductor devices that may benefit from aspects of the present disclosure.

[0014] As scales of the fin width in fin field effect transistors (FinFET) decreases, channel width variations might cause mobility loss. GAA transistors, such as nanosheet transistors are being studied as an alternative to fin field effect transistors. In a nanosheet transistor, the gate of the transistor is made all around the channel (e.g., a nanosheet channel or a nanowire channel) such that the channel is surrounded or encapsulated by the gate. Such a transistor has the advantage of

improving the electrostatic control of the channel by the gate, which also mitigates leakage currents.

[0015] In transistor gate stacks, the high-k gate dielectric compositions and/or thicknesses affect effective work functions of gate stacks and hence threshold voltages (V_{TH}) of transistors. Therefore, the GAA transistors having different threshold voltages can be achieved through the uses of different high-k gate dielectric compositions and/or thicknesses. For example, a gate stack of a high voltage (HV) device (e.g., input/output (I/O) device) may have more or fewer layers of high-k dielectric materials than a gate stack of a low voltage (LV) device (e.g., logic device), a gate stack of a p-type transistor may also have more or fewer layers of high-k dielectric materials than a gate stack of an n-type transistor. The gate stacks having different high-k dielectric compositions and/or thicknesses may be fabricated by using one or more photolithography and etching processes. For example, first and second high-k gate dielectric layers can be globally deposited over the first device region and the second device region, a hard mask layer is then deposited over the first and second high-k gate dielectric layers and patterned to expose the first device region or the second device region, followed by removing an exposed portion of the second high-k gate dielectric layer.

[0016] However, depositing the hard mask layer in spaces between neighboring nanosheets (interchangeably referred to as sheet-sheet spaces) may be accompanied by seam-holes, voids, or gaps in the hard mask layer in the sheet-sheet spaces. In a following photolithography process for patterning the hard mask layer, a bottom anti-reflective coating (BARC) may inadvertently flow into the seam-holes in hard mask layer, which in turn may leave BARC residues in the sheet-sheet spaces after the patterning the high-k gate dielectric layers, which in turn may impede following deposition of the gate metal materials in the sheet-sheet spaces.

[0017] Therefore, the present disclosure in various embodiments forms a hard mask layer by using an improved atomic layer deposition (ALD) process for seam-hole reduction. For example, the improved ALD process may reduce a number of seam-holes to an acceptable amount or to form a seam-free hard mask layer by controlling pulse time and/or purge time in the ALD process. A seam-free hard mask layer may aid in reducing the risk that the BARC flows in the sheet-sheet spaces. A hard mask layer having an acceptable amount of seam-holes may be advantageous for the hard mask removal process, because it takes less time to remove the hard mask layer by wet etching.

[0018] FIG. 1 illustrates an example of GAA-FETs (e.g., nanowire FETs, nanosheet FETs, or the like) in a three-dimensional view, in accordance with some embodiments. The GAA-FETs comprise nanostructures **104** (e.g., nanosheets, nanowires, nanorings, nanoslabs, or other structures having nano-scale size (e.g., a few nanometers)) over fins **102** on a substrate **100** (e.g., a semiconductor substrate), wherein the nanostructures **104** act as channel regions for the GAA-FETs. The nanostructure **104** may include p-type nanostructures, n-type nanostructures, or a combination thereof. Isolation regions **106** are disposed between adjacent fins **102**, which may protrude above and from between neighboring isolation regions **106**. Although the isolation regions **106** are described/illustrated as being separate from the substrate **100**, as used herein, the term “substrate” may refer to the semiconductor substrate alone or a combination of the semiconductor substrate and the isolation regions. Additionally, although a bottom portion of the fins **102** are illustrated as being single, continuous materials with the substrate **100**, the bottom portion of the fins **102** and/or the substrate **100** may comprise a single material or a plurality of materials. In this context, the fins **102** refer to the portion extending between the neighboring isolation regions **106**. [0019] Gate dielectrics **110** are over top surfaces of the fins **102** and along top surfaces, sidewalls, and bottom surfaces of the nanostructures **104**. Gate electrodes **112** are over the gate dielectrics **110**. Epitaxial source/drain regions **108** are disposed on the fins **102** on opposing sides of the gate dielectric layers **110** and the gate electrodes **112**.

[0020] FIG. 1 further illustrates reference cross-sections that are used in later figures. Cross-section A-A' is along a longitudinal axis of a gate electrode **112** and in a direction, for example,

perpendicular to the direction of current flow between the epitaxial source/drain regions **108** of a GAA-FET. Cross-section B-B' is perpendicular to cross-section A-A' and is parallel to a longitudinal axis of a fin **102** of the GAA-FET and in a direction of, for example, a current flow between the epitaxial source/drain regions **108** of the GAA-FET. Cross-section C-C' is parallel to cross-section A-A' and extends through epitaxial source/drain regions of the GAA-FETs. Subsequent figures refer to these reference cross-sections for clarity.

[0021] Some embodiments discussed herein are discussed in the context of GAA-FETs formed using a gate-last process. In other embodiments, a gate-first process may be used. Also, some embodiments contemplate aspects used in planar devices, such as planar FETs or in fin field-effect transistors (FinFETs).

[0022] FIGS. **2** through **24B** are cross-sectional views of intermediate stages in the manufacturing of GAA-FETs, in accordance with some embodiments. FIGS. **2** through **5**, **6A**, **13A**, **14A**, **15A**, **16A**, **17A**, **18A**, **19A**, **19C**, **19E**, **20A**, **20C**, **21A**, **22A**, **23A**, and **24A** illustrate reference cross-section A-A' illustrated in FIG. **1** that extends through a gate region along a longitudinal axis of the gate region. FIGS. **6B**, **7B**, **8B**, **9B**, **10B**, **11B**, **11C**, **12B**, **12D**, **13B**, **14B**, **15B**, **16B**, **17B**, **18B**, **19B**, **19D**, **20B**, **20D**, **21B**, **22B**, **23B**, and **24B** illustrate reference cross-section B-B' illustrated in FIG. **1** that extends through a fin along a longitudinal axis of the fin. FIGS. **7A**, **8A**, **9A**, **10A**, **11A**, **12A**, **12C**, and **13C** illustrate reference cross-section C-C' illustrated in FIG. **1** that extends through source/drain regions along the longitudinal direction of the gate region.

[0023] In FIG. **2**, a substrate **100** is provided. The substrate **100** may be a semiconductor substrate, such as a bulk semiconductor, a semiconductor-on-insulator (SOI) substrate, or the like, which may be doped (e.g., with a p-type or an n-type dopant) or undoped. The substrate **100** may be a wafer, such as a silicon wafer. Generally, an SOI substrate is a layer of a semiconductor material formed on an insulator layer. The insulator layer may be, for example, a buried oxide (BOX) layer, a silicon oxide layer, or the like. The insulator layer is provided on a substrate, typically a silicon or glass substrate. Other substrates, such as a multi-layered or gradient substrate may also be used. In some embodiments, the semiconductor material of the substrate **100** may include silicon; germanium; a compound semiconductor including silicon carbide, gallium arsenide, gallium phosphide, indium phosphide, indium arsenide, and/or indium antimonide; an alloy semiconductor including silicon-germanium, gallium arsenide phosphide, aluminum indium arsenide, aluminum gallium arsenide, gallium indium arsenide, gallium indium phosphide, and/or gallium indium arsenide phosphide; or combinations thereof.

[0024] The substrate **100** has a first device region **1001** and a second device region **1002**. The first device region **1001** is a region in which first transistors will reside, and the second device region **1002** is a region in which second transistors will reside. In some embodiments, the first transistors are different from the second transistors at least in threshold voltage. For example, first transistors in the first device region **1001** may be HV devices (e.g., I/O devices), and second transistors in the second device region **1002** may be LV devices (e.g., logic devices). In some other embodiments, the first transistors are different from the second transistors at least in conductivity type. For example, first device region **1001** can be for forming n-type devices, such as NMOS transistors, e.g., n-type GAA-FETs, and the second device region **1002** can be for forming p-type devices, such as PMOS transistors, e.g., p-type GAA-FETs.

[0025] The first device region **1001** may be separated from the second device region **1002**, and any number of device features (e.g., other active devices, doped regions, isolation structures, etc.) may be disposed between the first device region **1001** and the second device region **1002**. Although one first device region **1001** and one second device region **1002** are illustrated, any number of first device regions **1001** and second device regions **1002** may be provided.

[0026] Further in FIG. **2**, a multi-layer stack **201** is formed over the substrate **100**. The multi-layer stack **201** includes alternating layers of first semiconductor layers **202A-C** (collectively referred to as first semiconductor layers **202**) and second semiconductor layers **204A-C** (collectively referred

to as second semiconductor layers **204**). For purposes of illustration and as discussed in greater detail below, the first semiconductor layers **202** will be removed and the second semiconductor layers **204** will be patterned to form channel regions of GAA-FETs.

[0027] The multi-layer stack **201** is illustrated as including three layers of each of the first semiconductor layers **202** and the second semiconductor layers **204** for illustrative purposes. In some embodiments, the multi-layer stack **201** may include any number of the first semiconductor layers **202** and the second semiconductor layers **204**. Each of the layers of the multi-layer stack **201** may be epitaxially grown using a process such as chemical vapor deposition (CVD), atomic layer deposition (ALD), vapor phase epitaxy (VPE), molecular beam epitaxy (MBE), or the like. In various embodiments, the second semiconductor layers **204** may be formed of a semiconductor material suitable for serving as channel regions of GAA-FETs, such as silicon, silicon carbon, silicon germanium, or the like.

[0028] The first semiconductor materials and the second semiconductor materials may be materials having a high-etch selectivity to one another. As such, the first semiconductor layers **202** of the first semiconductor material may be removed without significantly removing the second semiconductor layers **204** of the second semiconductor material, thereby allowing the second semiconductor layers **204** to serve as channel regions of GAA-FETs.

[0029] Referring now to FIG. **3**, fin structures **206** are formed in the substrate **100** and nanostructures **203** are formed in the multi-layer stack **201**, in accordance with some embodiments. In some embodiments, the nanostructures **203** and the fin structures **206** may be formed in the multi-layer stack **201** and the substrate **100**, respectively, by etching trenches in the multi-layer stack **201** and the substrate **100**. Each fin structure **206** and overlying nanostructures **203** can be collectively referred to as a fin extending from the substrate **100**. The etching may be any acceptable etch process, such as a reactive ion etch (RIE), neutral beam etch (NBE), the like, or a combination thereof. The etching may be anisotropic. Forming the nanostructures **203** by etching the multi-layer stack **201** may further define first nanostructures **202A-C** (collectively referred to as the first nanostructures **202**) from the first semiconductor layers **202** and define second nanostructures **204A-C** (collectively referred to as the second nanostructures **204**) from the second semiconductor layers **204**. The first nanostructures **202** and the second nanostructures **204** may further be collectively referred to as nanostructures **203**.

[0030] The fin structures **206** and the nanostructures **203** may be patterned by any suitable method. For example, the fin structures **206** and the nanostructures **203** may be patterned using one or more photolithography processes, including double-patterning or multi-patterning processes. Generally, double-patterning or multi-patterning processes combine photolithography and self-aligned processes, allowing patterns to be created that have, for example, pitches smaller than what is otherwise obtainable using a single, direct photolithography process. For example, in one embodiment, a sacrificial layer is formed over a substrate and patterned using a photolithography process. Spacers are formed alongside the patterned sacrificial layer using a self-aligned process. The sacrificial layer is then removed, and the remaining spacers may then be used to pattern the fin structures **206**.

[0031] FIG. **3** illustrates the fin structures **206** in the first device region **1001** and the second device region **1002** as having substantially equal widths for illustrative purposes. In some embodiments, widths of the fin structures **206** in the first device region **1001** may be greater or thinner than the fin structures **206** in the second device region **1002**. Further, while each of the fin structures **206** and the nanostructures **203** are illustrated as having a consistent width throughout, in other embodiments, the fin structures **206** and/or the nanostructures **203** may have tapered sidewalls such that a width of each of the fin structures **206** and/or the nanostructures **203** continuously increases in a direction towards the substrate **100**. In such embodiments, each of the nanostructures **203** may have a different width and be trapezoidal in shape.

[0032] In FIG. **4**, shallow trench isolation (STI) regions **208** are formed adjacent the fin structures

206. The STI regions **208** may be formed by depositing an insulation material over the substrate **100**, the fin structures **206**, and nanostructures **203**, and between adjacent fin structures **206**. The insulation material may be an oxide, such as silicon oxide, a nitride, the like, or a combination thereof, and may be formed by high-density plasma CVD (HDP-CVD), flowable CVD (FCVD), the like, or a combination thereof. Other insulation materials formed by any acceptable process may be used. In the illustrated embodiment, the insulation material is silicon oxide formed by an FCVD process. An anneal process may be performed once the insulation material is formed. In an embodiment, the insulation material is formed such that excess insulation material covers the nanostructures **203**. Although the insulation material is illustrated as a single layer, some embodiments may utilize multiple layers. For example, in some embodiments a liner (not separately illustrated) may first be formed along a surface of the substrate **100**, the fin structures **206**, and the nanostructures **203**. Thereafter, a fill material, such as those discussed above may be formed over the liner.

[0033] A removal process is then applied to the insulation material to remove excess insulation material over the nanostructures **203**. In some embodiments, a planarization process such as a chemical mechanical polish (CMP), an etch-back process, combinations thereof, or the like may be utilized. The planarization process exposes the nanostructures **203** such that top surfaces of the nanostructures **203** and the insulation material are level after the planarization process is complete.

[0034] The insulation material is then recessed to form the STI regions **208**. The insulation material is recessed such that upper portions of fin structures **206** in the first and second device regions **1001** and protrude from between neighboring STI regions **208**. Further, the top surfaces of the STI regions **208** may have a flat surface as illustrated, a convex surface, a concave surface (such as dishing), or a combination thereof. The top surfaces of the STI regions **208** may be formed flat, convex, and/or concave by an appropriate etch. The STI regions **208** may be recessed using an acceptable etching process, such as one that is selective to the material of the insulation material (e.g., etches the material of the insulation material at a faster rate than the material of the fin structures **206** and the nanostructures **203**). For example, an oxide removal using, for example, dilute hydrofluoric (dHF) acid may be used.

[0035] The process described above with respect to FIGS. 2 through 4 is just one example of how the fin structures **206** and the nanostructures **203** may be formed. In some embodiments, the fin structures **206** and/or the nanostructures **203** may be formed using a mask and an epitaxial growth process. For example, a dielectric layer can be formed over a top surface of the substrate **100**, and trenches can be etched through the dielectric layer to expose the underlying substrate **100**. Epitaxial structures can be epitaxially grown in the trenches, and the dielectric layer can be recessed such that the epitaxial structures protrude from the dielectric layer to form the fin structures **206** and/or the nanostructures **203**. The epitaxial structures may comprise the alternating semiconductor materials discussed above, such as the first semiconductor materials and the second semiconductor materials. In some embodiments where epitaxial structures are epitaxially grown, the epitaxially grown materials may be in situ doped during growth, which may obviate prior and/or subsequent implantations, although in situ and implantation doping may be used together.

[0036] Additionally, the first semiconductor layers (and resulting nanostructures **202**) and the second semiconductor layers (and resulting nanostructures **204**) are illustrated and discussed herein as comprising the same materials in the second device region **1002** and the first device region **1001** for illustrative purposes only. As such, in some embodiments one or both of the first semiconductor layers and the second semiconductor layers may be different materials or formed in a different order in the first and second device regions **1001** and **1002**.

[0037] Further in FIG. 4, appropriate wells (not separately illustrated) may be formed in the fin structures **206**, the nanostructures **203**, and/or the STI regions **208**. In some embodiments with different well types in different device regions **1001** and **1002**, different implant steps for the first device region **1001** and the second device region **1002** may be achieved using a photoresist or other

masks (not separately illustrated). For example, a photoresist may be formed over the fin structures **206** and the STI regions **208** in the first device region **1001** and the second device region **1002**. The photoresist is patterned to expose the second device region **1002**. The photoresist can be formed by using a spin-on technique and can be patterned using acceptable photolithography techniques. Once the photoresist is patterned, a first impurity (e.g., n-type impurity such as phosphorus, arsenic, antimony, or the like) implant is performed in the second device region **1002**, and the photoresist may act as a mask to substantially prevent the first impurities from being implanted into the first device region **1001**. After the implant, the photoresist is removed, such as by an acceptable ashing process.

[0038] Following or prior to the implanting of the second device region **1002**, a photoresist or other masks (not separately illustrated) is formed over the fin structures **206**, the nanostructures **203**, and the STI regions **208** in the first device region **1001** and the second device region **1002**. The photoresist is then patterned to expose the first device region **1001**. The photoresist can be formed by using a spin-on technique and can be patterned using acceptable photolithography techniques. Once the photoresist is patterned, a second impurity (e.g., p-type impurity such as boron, boron fluoride, indium, or the like) implant may be performed in the first device region **1001**, and the photoresist may act as a mask to substantially prevent p-type impurities from being implanted into the second device region **1002**. After the implant, the photoresist may be removed, such as by an acceptable ashing process.

[0039] After one or more well implants of the first device region **1001** and the second device region **1002**, an anneal may be performed to repair implant damage and to activate the p-type and/or n-type impurities that were implanted. In some embodiments, the grown materials of epitaxial fins may be in situ doped during growth, which may obviate the implantations, although in situ and implantation doping may be used together.

[0040] In FIG. 5, a dummy dielectric layer **210** is formed on the fin structures **206** and/or the nanostructures **203**. The dummy dielectric layer **210** may be, for example, silicon oxide, silicon nitride, a combination thereof, or the like, and may be deposited or thermally grown according to acceptable techniques. A dummy gate layer **212** is formed over the dummy dielectric layer **210**, and a mask layer **214** is formed over the dummy gate layer **212**. The dummy gate layer **212** may be deposited over the dummy dielectric layer **210** and then planarized, such as by a CMP. The mask layer **214** may be deposited over the dummy gate layer **212**. The dummy gate layer **212** may be a conductive or non-conductive material and may be selected from a group including amorphous silicon, polycrystalline-silicon (polysilicon), poly-crystalline silicon-germanium (poly-SiGe), metallic nitrides, metallic silicides, metallic oxides, and metals. The dummy gate layer **212** may be deposited by physical vapor deposition (PVD), CVD, sputter deposition, or other techniques for depositing the selected material. The dummy gate layer **212** may be made of other materials that have a high etching selectivity from the etching of isolation regions. The mask layer **214** may include, for example, silicon nitride, silicon oxynitride, or the like. In this example, a single dummy gate layer **212** and a single mask layer **214** are formed across the first device region **1001** and the second device region **1002**. It is noted that the dummy dielectric layer **210** is shown covering only the fin structures **206** and the nanostructures **203** for illustrative purposes only. In some embodiments, the dummy dielectric layer **210** may be deposited such that the dummy dielectric layer **210** covers the STI regions **208**, such that the dummy dielectric layer **210** extends between the dummy gate layer **212** and the STI regions **208**.

[0041] FIGS. 6A through 24B illustrate various following steps in the manufacturing of embodiment devices. FIGS. 6A, 7A, 8A, 9A, 10A, 11A, 12A, 12C, 13A, 13C, 14A, and 15A illustrate features in either the first device regions **1001** or the second device regions **1002**. In FIGS. 6A and 6B, the mask layer **214** (see FIG. 5) may be patterned using acceptable photolithography and etching techniques to form masks **218**. The pattern of the masks **218** then may be transferred to the dummy gate layer **212** and to the dummy dielectric layer **210** to form

dummy gates **216** and dummy gate dielectrics **211**, respectively. The dummy gates **216** cover respective channel regions of the fin structures **206**. The pattern of the masks **218** may be used to physically separate each of the dummy gates **216** from adjacent dummy gates **216**. The dummy gates **216** may also have a lengthwise direction substantially perpendicular to the lengthwise direction of respective fin structures **206**.

[0042] In FIGS. **7A** and **7B**, a first spacer layer **220** and a second spacer layer **222** are formed over the structures illustrated in FIGS. **6A** and **6B**, respectively. The first spacer layer **220** and the second spacer layer **222** will be subsequently patterned to act as spacers for forming self-aligned source/drain regions. In FIGS. **7A** and **7B**, the first spacer layer **220** is formed on top surfaces of the STI regions **208**; top surfaces and sidewalls of the fin structures **206**, the nanostructures **203**, and the masks **218**; and sidewalls of the dummy gates **216** and the dummy gate dielectric **211**. The second spacer layer **222** is deposited over the first spacer layer **220**. The first spacer layer **220** may be formed of silicon oxide, silicon nitride, silicon oxynitride, or the like, using techniques such as thermal oxidation or deposited by CVD, ALD, or the like. The second spacer layer **222** may be formed of a material having a different etch rate than the material of the first spacer layer **220**, such as silicon oxide, silicon nitride, silicon oxynitride, or the like, and may be deposited by CVD, ALD, or the like.

[0043] In FIGS. **8A** and **8B**, the first spacer layer **220** and the second spacer layer **222** are etched to form first spacers **221** and second spacers **223**. As will be discussed in greater detail below, the first spacers **221** and the second spacers **223** act to self-align subsequently formed source and drain regions, as well as to protect sidewalls of the fin structures **206** and/or nanostructure **203** during subsequent processing. The first spacer layer **220** and the second spacer layer **222** may be etched using a suitable etching process, such as an isotropic etching process (e.g., a wet etching process), an anisotropic etching process (e.g., a dry etching process), or the like. In some embodiments, the material of the second spacer layer **222** has a different etch rate than the material of the first spacer layer **220**, such that the first spacer layer **220** may act as an etch stop layer when patterning the second spacer layer **222** and such that the second spacer layer **222** may act as a mask when patterning the first spacer layer **220**. For example, the second spacer layer **222** may be etched using an anisotropic etch process wherein the first spacer layer **220** acts as an etch stop layer, wherein remaining portions of the second spacer layer **222** form second spacers **223** as illustrated in FIG. **8A**. Thereafter, the second spacers **223** acts as a mask while etching exposed portions of the first spacer layer **220**, thereby forming first spacers **221** as illustrated in FIG. **8A**.

[0044] As illustrated in FIG. **8A**, the first spacers **221** and the second spacers **223** are disposed on sidewalls of the fin structures **206** and/or nanostructures **203**. In some embodiments, the spacers **221** and **223** only partially remain on sidewalls of the fin structures **206**. In some embodiments, no spacer remains on sidewalls of the fin structures **206**. As illustrated in FIG. **8B**, in some embodiments, the second spacer layer **222** may be removed from over the first spacer layer **220** adjacent the masks **218**, the dummy gates **216**, and the dummy gate dielectrics **211**, and the first spacers **221** are disposed on sidewalls of the masks **218**, the dummy gates **216**, and the dummy dielectric layers **211**. In other embodiments, a portion of the second spacer layer **222** may remain over the first spacer layer **220** adjacent the masks **218**, the dummy gates **216**, and the dummy gate dielectrics **211**.

[0045] The above disclosure generally describes a process of forming spacers. Other processes and sequences may be used. For example, fewer or additional spacers may be utilized, different sequence of steps may be utilized (e.g., the first spacers **221** may be patterned prior to depositing the second spacer layer **222**), additional spacers may be formed and removed, and/or the like. Furthermore, devices in first device region **1001** and devices in the second device region **1002** may be formed using different structures and steps.

[0046] In FIGS. **9A** and **9B**, source/drain recesses **226** are formed in the fin structures **206**, the nanostructures **203**, and the substrate **100**, in accordance with some embodiments. Epitaxial

source/drain regions will be subsequently formed in the source/drain recesses **226**. The source/drain recesses **226** may extend through the first nanostructures **202** and the second nanostructures **204**, and into the substrate **100**. As illustrated in FIG. **9A**, bottom surfaces of the source/drain recesses **226** may be level with top surfaces of the STI regions **208**, as an example. In some other embodiments, the fin structures **206** may be etched such that bottom surfaces of the source/drain recesses **226** are disposed below the top surfaces of the STI regions **208**, or above the top surfaces of the STI regions **208**. The source/drain recesses **226** may be formed by etching the fin structures **206**, the nanostructures **203**, and the substrate **100** using anisotropic etching processes, such as RIE, NBE, or the like. The first spacers **221**, the second spacers **223**, and the masks **218** mask portions of the fin structures **206**, the nanostructures **203**, and the substrate **100** during the etching processes used to form the source/drain recesses **226**. A single etch process or multiple etch processes may be used to etch each layer of the nanostructures **203** and/or the fin structures **206**. Timed etch processes may be used to stop the etching of the source/drain recesses **226** after the source/drain recesses **226** reach a target depth.

[0047] In FIGS. **10A** and **10B**, portions of sidewalls of the layers of the multi-layer stack **201** formed of the first semiconductor materials (e.g., the first nanostructures **202**) exposed by the source/drain recesses **226** are etched to form sidewall recesses **228** between corresponding second nanostructures **204**. Although sidewalls of the first nanostructures **202** in recesses **228** are illustrated as being straight in FIG. **10B**, the sidewalls may be concave or convex. The sidewalls may be etched using isotropic etching processes, such as wet etching or the like. In some embodiments in which the first nanostructures **202** include, e.g., SiGe, and the second nanostructures **204** include, e.g., Si or SiC, a dry etch process with tetramethylammonium hydroxide (TMAH), ammonium hydroxide (NH₄OH), or the like may be used to etch sidewalls of the first nanostructures **202**.

[0048] In FIGS. **11A-11C**, inner spacers **230** are formed in the sidewall recess **228**. The inner spacers **230** may be formed by depositing an inner spacer layer (not separately illustrated) over the structures illustrated in FIGS. **10A** and **10B**. The inner spacers **230** act as isolation features between subsequently formed source/drain regions and gate structure. As will be discussed in greater detail below, source/drain regions will be formed in the recesses **226**, and the first nanostructures **202** will be replaced with corresponding gate structures.

[0049] The inner spacer layer may be deposited by a conformal deposition process, such as CVD, ALD, or the like. The inner spacer layer may comprise a material such as silicon nitride or silicon oxynitride, although any suitable material, such as low-dielectric constant (low-k) materials having a k-value less than about 3.5, may be utilized. The inner spacer layer may then be anisotropically etched to form the inner spacers **230**. Although outer sidewalls of the inner spacers **230** are illustrated as being flush with sidewalls of the second nanostructures **204**, the outer sidewalls of the inner spacers **230** may extend beyond or be recessed from sidewalls of the second nanostructures **204**.

[0050] Moreover, although the outer sidewalls of the inner spacers **230** are illustrated as being straight in FIG. **11B**, the outer sidewalls of the inner spacers **230** may be concave or convex. As an example, FIG. **11C** illustrates an embodiment in which sidewalls of the first nanostructures **202** are concave, outer sidewalls of the inner spacers **230** are concave, and the inner spacers are recessed from sidewalls of the second nanostructures **204**. The inner spacer layer may be etched by an anisotropic etching process, such as RIE, NBE, or the like. The inner spacers **230** may be used to prevent damage to subsequently formed source/drain regions (such as the epitaxial source/drain regions **232**, discussed below with respect to FIGS. **12A-12D**) by subsequent etching processes, such as etching processes used to form gate structures.

[0051] In FIGS. **12A-12D**, epitaxial source/drain regions **232** are formed in the source/drain recesses **226**. In some embodiments, the source/drain regions **232** may exert stress on the second nanostructures **204**, thereby improving device performance. As illustrated in FIG. **12B**, the

epitaxial source/drain regions **232** are formed in the source/drain recesses **226** such that each dummy gate **216** is disposed between respective neighboring pairs of the epitaxial source/drain regions **232**. In some embodiments, the first spacers **221** are used to separate the epitaxial source/drain regions **232** from the dummy gates **216** and the inner spacers **230** are used to separate the epitaxial source/drain regions **232** from the first nanostructures **202** by an appropriate lateral distance so that the epitaxial source/drain regions **232** do not short out with subsequently formed gates of the resulting GAA-FETs.

[0052] In some embodiments, the epitaxial source/drain regions **232** may include any acceptable material appropriate for n-type GAA-FETs. For example, if the second nanostructures **204** are silicon, the epitaxial source/drain regions **232** may include materials exerting a tensile strain on the second nanostructures **204**, such as silicon carbide, phosphorous doped silicon carbide, silicon phosphide, or the like. In some embodiments, the epitaxial source/drain regions **232** may include any acceptable material appropriate for p-type GAA-FETs. For example, if the second nanostructures **204** are silicon, the epitaxial source/drain regions **232** may comprise materials exerting a compressive strain on the second nanostructures **204**, such as silicon germanium, boron doped silicon germanium, germanium, germanium tin, or the like. The epitaxial source/drain regions **232** may have surfaces raised from respective upper surfaces of the nanostructures **203** and may have facets.

[0053] The epitaxial source/drain regions **232** may be implanted with dopants to form source/drain regions, followed by an anneal. The source/drain regions may have an impurity concentration of between about 1×10^{17} atoms/cm³ and about 1×10^{22} atoms/cm³. The n-type and/or p-type impurities for source/drain regions may be any of the impurities previously discussed. In some embodiments, the epitaxial source/drain regions **232** may be in situ doped during growth.

[0054] As a result of the epitaxy processes used to form the epitaxial source/drain regions **232**, upper surfaces of the epitaxial source/drain regions **232** have facets which expand laterally outward beyond sidewalls of the nanostructures **203**. In some embodiments, these facets cause adjacent epitaxial source/drain regions **232** to merge as illustrated by FIG. **12A**. In some other embodiments, adjacent epitaxial source/drain regions **232** remain separated after the epitaxy process is completed as illustrated by FIG. **12C**. In the embodiments illustrated in FIGS. **12A** and **12C**, the first spacers **221** may be formed to a top surface of the STI regions **208** thereby blocking the lateral epitaxial growth. In some other embodiments, the first spacers **221** may cover portions of the sidewalls of the nanostructures **203** further blocking the epitaxial growth. In some other embodiments, the spacer etch used to form the first spacers **221** may be adjusted to remove the spacer material to allow the epitaxially grown region to extend to the surface of the STI region **208**.

[0055] The epitaxial source/drain regions **232** may comprise one or more semiconductor material layers. For example, the epitaxial source/drain regions **232** may comprise a first semiconductor material layer **232A**, a second semiconductor material layer **232B**, and a third semiconductor material layer **232C**. Any number of semiconductor material layers may be used for the epitaxial source/drain regions **232**. Each of the first semiconductor material layer **232A**, the second semiconductor material layer **232B**, and the third semiconductor material layer **232C** may be formed of different semiconductor materials and may be doped to different dopant concentrations. In some embodiments, the first semiconductor material layer **232A** may have a dopant concentration less than the second semiconductor material layer **232B** and greater than the third semiconductor material layer **232C**. In embodiments in which the epitaxial source/drain regions **232** comprise three semiconductor material layers, the first semiconductor material layer **232A** may be deposited, the second semiconductor material layer **232B** may be deposited over the first semiconductor material layer **232A**, and the third semiconductor material layer **232C** may be deposited over the second semiconductor material layer **232B**.

[0056] FIG. **12D** illustrates an embodiment in which sidewalls of the first nanostructures **202** are

concave, outer sidewalls of the inner spacers **230** are concave, and the inner spacers **230** are recessed from sidewalls of the second nanostructures **204**. As illustrated in FIG. **12D**, the epitaxial source/drain regions **232** may be formed in contact with the inner spacers **230** and may extend past sidewalls of the second nanostructures **204**.

[0057] In FIGS. **13A-13C**, an interlayer dielectric (ILD) layer **236** is deposited over the structure illustrated in FIGS. **12A-12D**. The ILD layer **236** may be formed of a dielectric material, and may be deposited by any suitable method, such as CVD, plasma-enhanced CVD (PECVD), or FCVD. Dielectric materials may include phospho-silicate glass (PSG), boro-silicate glass (BSG), boron-doped phospho-silicate glass (BPSG), undoped silicate glass (USG), or the like. Other insulation materials formed by any acceptable process may be used. In some embodiments, a contact etch stop layer (CESL) **234** is disposed between the ILD layer **236** and the epitaxial source/drain regions **232**, the masks **218**, and the first spacers **221**. The CESL **234** may comprise a dielectric material, such as, silicon nitride, silicon oxide, silicon oxynitride, or the like, having a different etch rate than the material of the overlying ILD layer **236**.

[0058] In FIGS. **14A-14B**, a planarization process, such as a CMP, may be performed to level the top surface of the ILD layer **236** with the top surfaces of the dummy gates **216** or the masks **218**. The planarization process may also remove the masks **218** on the dummy gates **216**, and portions of the first spacers **221** along sidewalls of the masks **218**. After the planarization process, top surfaces of the dummy gates **216**, the first spacers **221**, and the ILD layer **236** are level within process variations. Accordingly, the top surfaces of the dummy gates **216** are exposed through the ILD layer **236**. In some embodiments, the masks **218** may remain, in which case the planarization process levels the top surface of the ILD layer **236** with top surface of the masks **218** and the first spacers **221**.

[0059] In FIGS. **15A** and **15B**, the dummy gates **216**, and the masks **218** if present, are removed in one or more etching steps, so that gate trenches **238** are formed between corresponding gate spacers **221**. In some embodiments, portions of the dummy gate dielectrics **211** in the gate trenches **238** are also be removed. In some embodiments, the dummy gates **216** and the dummy gate dielectrics **211** are removed by an anisotropic dry etch process. For example, the etching process may include a dry etch process using reaction gas(es) that selectively etch the dummy gates **216** at a faster rate than the ILD layer **236** or the first spacers **221**. Each gate trench **238** exposes and/or overlies portions of nanostructures **204**, which act as channel regions in subsequently completed GAA-FETs. The nanostructures **204** which act as the channel regions are disposed between neighboring pairs of the epitaxial source/drain regions **232**. During the removal, the dummy dielectric layers **211** may be used as etch stop layers when the dummy gates **216** are etched. The dummy dielectric layers **211** may then be removed after the removal of the dummy gates **216**.

[0060] In FIGS. **16A** and **16B**, the first nanostructures **202** in the gate trenches are removed by an isotropic etching process such as wet etching or the like using etchants which are selective to the materials of the first nanostructures **202**. Stated differently, the first nanostructures **202** are removed by using a selective etching process that etches the first nanostructures **202** at a faster etch rate than it etches the second nanostructures **204**, thus forming spaces between the second nanostructures **204** (also referred to as sheet-sheet spaces if the nanostructures **204** are nanosheets). This step can be referred to as a channel release process. At this interim processing step, the spaces between second nanostructures **204** may be filled with ambient environment conditions (e.g., air, nitrogen, etc). In some embodiments, the second nanostructures **204** can be referred to as nanosheets, nanowires, nanoslabs, nanorings having nano-scale size (e.g., a few nanometers), depending on their geometry. For example, in some embodiments the second nanostructures **204** may be trimmed to have a substantial rounded shape (i.e., cylindrical) due to the selective etching process for completely removing the first nanostructures **202**. In that case, the resultant second nanostructures **204** can be called nanowires.

[0061] In embodiments in which the first nanostructures **202** include, e.g., SiGe, and the second

nanostuctures **204** include, e.g., Si or SiC, tetramethylammonium hydroxide (TMAH), ammonium hydroxide (NH₄OH) or the like may be used to remove the first nanostructures **202**. In some embodiments, both the channel release step and the previous step of laterally recessing first nanostructures **202** (i.e., the step as illustrated in FIGS. **10A-10B**) use a selective etching process that etches first nanostructures **202** (e.g., SiGe) at a faster etch rate than etching second nanostructures **204** (e.g., Si), and therefore these two steps may use the same etchant chemistry in some embodiments. In this case, the etching time/duration of channel release step is longer than the etching time/duration of the previous step of laterally recessing first nanostructures **202**, so as to completely remove the sacrificial nanostructures **202**.

[0062] In FIGS. **17A** and **17B**, gate dielectrics are deposited conformally in the gate trenches **238** in both the first device region **1001** and the second device region **1002**. The gate dielectrics comprise one or more dielectric layers, such as an oxide, one or more metal oxides, the like, or combinations thereof. For example, in some embodiments, the gate dielectrics may comprise a first gate dielectric layer **240** and a second gate dielectric layer **242** over the first gate dielectric layer **240**. In some embodiments, the first and second gate dielectric layers **240** and **242** both include a high-k dielectric material, and in these embodiments, the first and second gate dielectric layers **240** and **242** may have a k value greater than about **7.0**, and may include a metal oxide or a silicate of hafnium, aluminum, zirconium, lanthanum, manganese, barium, titanium, lead, and combinations thereof. In some embodiments, the first gate dielectric layer **240** comprises a different high-k dielectric material than the second gate dielectric layer **242**. For example, the first high-k gate dielectric layer **240** is made of hafnium oxide (HfO₂), and the second high-k gate dielectric layer **242** is made of lanthanum oxide (La₂O₃). The gate dielectric layers **240** and **242** may be globally deposited over the first and second device regions **1001** and **1002** by using, for example, molecular-beam deposition (MBD), ALD, PECVD, or the like.

[0063] In FIGS. **18A** through **19E**, a hard mask layer **244** is deposited on the gate trenches **238** in both the first device region **1001** and the second device region **1002**. In some embodiments, the hard mask layer **244** includes aluminum oxide (AlO_x), which is deposited over the second gate dielectric layer **242** by using an ALD process performed in an ALD tool.

[0064] FIG. **25** illustrates an example ALD tool **300** that may be utilized to form the hard mask layer **244**. In some embodiments, the ALD tool **300** may receive precursor materials from a first precursor delivery system **305** and a second precursor delivery system **307**, and form the hard mask layer **244** onto the second gate dielectric layer **242** over the substrate **100**. The formation of the hard mask layer may be performed in a deposition chamber **303** which receives the first precursor material and the second precursor material.

[0065] The first precursor delivery system **305** and the second precursor delivery system **307** may work in conjunction with one another to supply the various different precursor materials to the deposition chamber **303** where the substrate **100** is placed. The first precursor delivery system **305** and the second precursor delivery system **307** may have physical components that are similar with each other. In other embodiments, fewer or more precursor delivery systems may be used.

[0066] For example, the first precursor delivery system **305** and the second precursor delivery system **307** may each include a gas supply **308** and a flow controller **309**. In some embodiment in which the first precursor material is stored in a gaseous state, the gas supply **308** may supply the first precursor material to the deposition chamber **303**. The gas supply **308** may be a vessel, such as a gas storage tank, that is located either locally to the deposition chamber **303** or else may be located remotely from the deposition chamber **303**. Alternatively, the gas supply **308** may be a facility that independently prepares and delivers the first precursor material to the flow controller **309**. Any suitable source for the first precursor material may be utilized as the gas supply **308**, and all such sources are fully intended to be included within the scope of the embodiments.

[0067] The gas supply **308** may supply the desired precursor to the flow controller **309**. The flow controller **309** may be used to control the flow of the precursor to the gas controller **313** and,

eventually, to the deposition chamber **303**, thereby also helping to control the pressure within the deposition chamber **303**. The flow controller **309** may be, e.g., a proportional valve, a modulating valve, a needle valve, a pressure regulator, a mass flow controller, combinations of these, or the like. However, any suitable method for controlling and regulating the flow of the precursor materials may be used, and all such components and methods are fully intended to be included within the scope of the embodiments.

[0068] However, it is understood that, while the first precursor delivery system **305** and the second precursor delivery system **307** have been described herein as having identical components, this is merely an illustrative example and is not intended to limit the embodiments in any fashion. Any type of suitable precursor delivery system, with any type and number of individual components identical to or different from any of the other precursor delivery systems within the ALD tool **300**, may alternatively be utilized. All such precursor systems are fully intended to be included within the scope of the embodiments.

[0069] Additionally, in an embodiment in which the first precursor material is stored in a solid or liquid state, the gas supply **308** may store a carrier gas and the carrier gas may be introduced into a precursor canister (not separately illustrated), which stores the first precursor in the solid or liquid state. The carrier gas is then used to push and carry the first precursor as it either evaporates or sublimates into a gaseous section of the precursor canister before being sent to the gas controller **313**. Any suitable method and combination of units may be utilized to provide the first precursor, and all such combination of units are fully intended to be included within the scope of the embodiments. In some embodiments, the carrier gas may be nitrogen (N.sub.2), helium (He), argon (Ar), combinations of these, or the like, although other suitable carrier gases may alternatively be used.

[0070] The first precursor delivery system **305** and the second precursor delivery system **307** may supply their individual precursor materials into a gas controller **313**. The gas controller **313** connects and isolates the first precursor delivery system **305** and the second precursor delivery system **307**, from the deposition chamber **303** in order to deliver the desired precursor materials to the deposition chamber **303**. The gas controller **313** may include such devices as valves, flow meters, sensors, and the like to control the delivery rates of each of the precursors, and may be controlled by instructions received from the control unit **315**. In some embodiments a purge gas delivery system **314** may be connected to the gas controller **313** and provide a purge gas to the deposition chamber **303**. The purge gas delivery system **314** may include a gaseous tank or other facility that provides a purge gas such as nitrogen (N.sub.2), helium (He), argon (Ar), xenon (Xe), or combinations of these, or the like, or other non-reactive gas to the deposition chamber **303**.

[0071] The gas controller **313**, upon receiving instructions from the control unit **315**, may open and close valves so as to connect one or more of the first precursor delivery system **305** or the second delivery system **307** to the deposition chamber **303** and direct a desired precursor material through a manifold **316** to a showerhead **317** in the deposition chamber **303**. The showerhead **317** may be used to disperse the chosen precursor materials into the deposition chamber **303** and may be designed to evenly disperse the precursor materials in order to minimize undesired process conditions that may arise from uneven dispersal. In an embodiment the showerhead **317** may have a circular design with openings dispersed evenly around the showerhead **317** to allow for the dispersal of the desired precursor materials into the deposition chamber **303**.

[0072] However, the introduction of precursor materials to the deposition chamber **303** through a single showerhead **317** or through a single point of introduction as described above is intended to be illustrative only and is not intended to be limiting to the embodiments. Any number of separate and independent showerheads **317** or other openings to introduce precursor materials into the deposition chamber **303** may alternatively be used. All such combinations of showerheads and other points of introduction are fully intended to be included within the scope of the embodiments.

[0073] The deposition chamber **303** may receive the desired precursor materials and expose the

precursor materials to the semiconductor device **100**. The deposition chamber **303** may be any desired shape that may be suitable for dispersing the precursor materials and contacting the precursor materials with the semiconductor device **100**. In the embodiment illustrated in FIG. 25, the deposition chamber **303** has a cylindrical sidewall and a bottom. However, the deposition chamber **303** is not limited to a cylindrical shape, and any other suitable shape, such as a hollow square tube, an octagonal shape, or the like, may be used. Furthermore, the deposition chamber **303** may be surrounded by a housing **319** made of material that is inert to the various process materials. As such, while the housing **319** may be any suitable material that can withstand the chemistries and pressures involved in the deposition process, in an embodiment the housing **319** may be steel, stainless steel, nickel, aluminum, alloys of these, combinations of these, and like.

[0074] Within the deposition chamber **303** the semiconductor wafer **100** may be placed on a mounting platform **331** in order to position and control the semiconductor wafer **100** during the deposition processes. The mounting platform **331** may include a heater **332** or other heating mechanism in order to heat the semiconductor wafer **100** during the ALD process. Furthermore, while a single mounting platform **331** is illustrated in FIG. 25, any number of mounting platforms **331** may additionally be included within the deposition chamber **303**.

[0075] Additionally, the deposition chamber **303** and the mounting platform **331** may be part of a cluster tool system (not shown). The cluster tool system may be used in conjunction with an automated handling system in order to position and place the semiconductor wafer **100** into the deposition chamber **303** prior to the ALD processes, position, hold the semiconductor wafer **100** during the ALD process, and remove the semiconductor wafer **100** from the deposition chamber **303** after the deposition process.

[0076] The deposition chamber **303** may also have an exhaust outlet **325** for exhaust gases to exit the deposition chamber **303**. A vacuum pump **323** may be connected to the exhaust outlet **325** of the deposition chamber **303** in order to help evacuate the exhaust gases. The vacuum pump **323**, under control of the control unit **315**, may also be utilized to reduce and control the pressure within the deposition chamber **303** to a desired pressure and may also be used to evacuate precursor materials or reaction byproducts from the deposition chamber **303** in preparation for another step of the deposition process.

[0077] The tool **300** of FIG. 25 may be utilized to form the hard mask layer **244** through an ALD process as illustrated in FIGS. 18A-19E, wherein FIGS. 18A and 18B illustrate cross-sectional views of an initial stage of the ALD film growth, and FIGS. 19A-19E illustrate cross-sectional views of various embodiments of a final stage of the ALD film growth. Referring now to FIG. 26, a summary of an embodiment ALD process flow of forming the hard mask layer **244** is illustrated. In some embodiments where the hard mask layer **244** is a binary compound such as aluminum oxide, the ALD process includes one or more deposition cycles **410** to deposit one or more monolayers of aluminum oxide. Each deposition cycle **410** includes pulsing an oxygen-containing precursor into an ALD chamber (step **412**) for a first pulse time T1, purging the oxygen-containing precursor from the ALD chamber (step **414**) for a first purge time T2, pulsing an aluminum-containing precursor into the ALD chamber (step **416**) for a second pulse time T3, and purging the aluminum-containing precursor from the ALD chamber (step **418**) for a second purge time T4. The aluminum-containing precursor reacts with the oxygen-containing precursor to deposit a monolayer of aluminum oxide on exposed surfaces of the second gate dielectric layer **242**. Each deposition cycle **410** deposits a single monolayer of aluminum oxide, and any number of deposition cycles **410** may be performed to deposit a target quantity of titanium nitride monolayers. It is observed that pulsing the oxygen-containing precursor before pulsing the aluminum-containing precursor in each cycle may achieve a better aluminum oxide film quality (e.g., better thickness uniformity) than pulsing the aluminum-containing precursor before pulsing the oxygen-containing precursor. Therefore, the sequence of pulsing the oxygen-containing precursor prior to pulsing the aluminum-containing precursor can aid in improving the resultant aluminum oxide film quality.

[0078] If the oxygen-containing precursor pulse time T1 and/or the aluminum-containing precursor pulse time T3 are shorter than 1 second, overhangs 244o may be formed at each corner 242c of the second gate dielectric layer 242, as illustrated in FIGS. 19C and 19D. In some embodiments, as the ALD cycle 410 repeats, the overhangs 244o would extend toward each other to form seam-holes, voids or gaps GP in each space 243 between neighboring nanostructures 204 (interchangeably referred to as sheet-sheet spaces), as illustrated in FIG. 19C. In some embodiments, as the ALD cycles 410 repeats, the overhangs 244o may merge, sealing off the sheet-sheet spaces 243 with seam-holes, voids or gaps GP sealed in each sheet-sheet space 243, as illustrated in FIGS. 19D and 19E. In the scenario of FIG. 19C, a BARC material may inadvertently flow into the seam-holes GP in a following BARC coating process (as illustrated in FIG. 20C), which in turn may leave BARC residues in the sheet-sheet spaces 243, thus impeding following deposition of gate metal materials in the sheet-sheet spaces 243.

[0079] Therefore, in some embodiments of the present disclosure, the oxygen-containing precursor pulse time T1 and/or the aluminum-containing precursor pulse time T3 are lengthened to reduce a number of seam-holes GP in the hard mask layer 244 to an acceptable amount, or to form a seam-free hard mask layer 244. For example, the oxygen-containing precursor is pulsed for the pulse time T1 greater than about 1 second, about 2 seconds, about 3 seconds, about 4 seconds, about 5 seconds, about 6 seconds, or even more, and the aluminum-containing precursor is pulsed for the pulse time T3 greater than about 1 second, about 2 seconds, about 3 seconds, about 4 seconds, about 5 seconds, about 6 seconds, or even more. When the oxygen-containing precursor pulse time T1 and/or the aluminum-containing precursor pulse time T3 are great than about 1 second, the pulse time durations are long enough to aid in diffusing the oxygen-containing precursor and/or the aluminum-containing precursor deeper into the sheet-sheet spaces 243, which in turn can inhibit formation of overhangs at some or all corners 242c of the second gate dielectric layer 242, which in turn can reduce the number or percentage of seam-holes GP in the hard mask layer 244. Seam-hole percentage in this context may be referred to as a ratio of total seam-hole size of all seam holes to a size of the hard mask layer. A seam-free hard mask layer 244 (as illustrated in FIG. 19A) may aid in reducing the risk that BARC flows in the sheet-sheet spaces 243 in following processing. A hard mask layer having an acceptable amount of seam-holes may be advantageous for following hard mask removal process, because it takes less time to remove the hard mask layer by wet etching.

[0080] Moreover, in some embodiments, the oxygen-containing precursor purge time T2 and/or the aluminum-containing precursor purge time T3 are lengthened to get rid of by-products resulting from the oxygen-containing precursor pulse step 412 and/or the aluminum-containing precursor pulse step 416, which in turn can reduce the risk that by-products merge above the topmost nanostructure 204C in the gate trench in the cross-section of FIG. 19B.

[0081] In some embodiments, the oxygen-containing precursor purge time T2 is at least about fifteen times the oxygen-containing precursor pulse time T1. Because the oxygen-containing precursor pulse time T1 is more than about 1 second, the oxygen-containing precursor purge time T2 is more than about 15 seconds. Similarly, if the oxygen-containing precursor pulse time T1 is more than 2 second, the oxygen-containing precursor purge time T2 is more than about 30 seconds, and so on. In some embodiments, the aluminum-containing precursor purge time T4 is at least about ten times the aluminum-containing precursor pulse time T3. Because the aluminum-containing precursor pulse time T3 is more than about 1 second, the aluminum-containing precursor purge time T4 is more than about 10 seconds. Similarly, if the aluminum-containing precursor pulse time T3 is more than 2 second, the aluminum-containing precursor purge time T4 is more than about 20 seconds, and so on.

[0082] In some embodiments, a ratio of the oxygen-containing precursor purge time T2 to the oxygen-containing precursor pulse time T1 is greater than a ratio of the aluminum-containing precursor purge time T4 to the aluminum-containing precursor pulse time T3, because it is easier to purge out the aluminum-containing precursor gas (e.g., TMA) than purging out the oxygen-

containing precursor gas (e.g., H.sub.2O). For example, the ratio of the oxygen-containing precursor purge time T2 to the oxygen-containing precursor pulse time T1 is at least about 15:1, and the ratio of the aluminum-containing precursor purge time T4 to the aluminum-containing precursor pulse time T3 is at least about 10:1.

[0083] In some embodiments, the oxygen-containing precursor pulse time T1 is substantially the same as the aluminum-containing precursor pulse time T3. In this scenario, the oxygen-containing precursor purge time T2 is longer than the aluminum-containing precursor purge time T4. For example, when the oxygen-containing precursor pulse time T1 is substantially the same as the aluminum-containing precursor pulse time T3, a ratio of the oxygen-containing precursor purge time T2 to the aluminum-containing precursor purge time T4 is about 3:2. For example, when the oxygen-containing precursor pulse time T1 and the aluminum-containing precursor pulse time T3 are the same and both greater than about 1 second, the oxygen-containing precursor purge time T2 is greater than about 15 seconds, and the aluminum-containing precursor purge time T4 is greater than about 10 seconds and less than the oxygen-containing precursor purge time T2.

[0084] In some embodiments, the aluminum-containing precursor used in the ALD deposition cycle 410 includes, for example, trimethylaluminum, the chemical compound with the formula Al.sub.2(CH.sub.3).sub.6, abbreviated as Al.sub.2Me.sub.6, (AlMe.sub.3).sub.2 or the abbreviation TMA. In some embodiments, the oxygen-containing precursor used in the ALD deposition cycle 410 is water (H.sub.2O), oxygen (O.sub.2), ozone (O.sub.3), hydrogen peroxide (H.sub.2O.sub.2), or the like. In some embodiments, the ALD deposition cycle 410 uses H.sub.2O as the first precursor and TMA as the second precursor. In some embodiments, in each step in the ALD deposition cycle 410, the deposition chamber may be held at a constant pressure (isobaric) lower than about 1.5 torr, and a constant temperature (isothermal) greater than about 250° C. In some embodiments, the number of deposition cycles 410 is in a range from about 20 to about 60. If the process conditions (e.g., pressure, temperature, and cycle number) are outside the above selected ranges, the hard mask layer 244 may be formed with an unacceptable number or percentage of seam-holes.

[0085] In the embodiments as discussed above the hard mask layer 244 is made of aluminum oxide. However, in some other embodiments, other materials may be used as the hard mask layer 244, as long as the hard mask layer 244 has an etch selectivity with an underlying layer (e.g., the second gate dielectric layer 242) to be patterned. By way of example and not limitation, the hard mask layer 244 may include titanium oxide (TiO.sub.x), zirconium oxide (ZrO.sub.x), zinc oxide (ZnO), tin oxide (SnO.sub.x), silicon nitride, silicon carbide, silicon carbon nitride, combinations or multiple layers or the like. In some embodiments, the ALD process for forming these materials may use a first precursor gas and a second precursor gas, wherein the first precursor gas may include, for example, diethyl zinc (DEZ, Zn(C.sub.2H.sub.5).sub.2), tetrakis(dimethylamino)titanium (TDMAT, Ti[(CH.sub.3).sub.2N].sub.4), titanium isopropoxide (TTIP, Ti[(CH.sub.3).sub.2OCH].sub.4), titanium tetrachloride (TiCl.sub.4), bis(tertiary-butyl-amino)silane (BTBAS, [NH(C.sub.4H.sub.9)].sub.2SiH.sub.2), bis(diethylamino)silane (BDIS, SiH.sub.2[N(C.sub.2H.sub.5).sub.2].sub.2), tris(dimethylamino)silane (.sub.3DMAS, SiH[N(CH.sub.3).sub.2].sub.3), tetrakis(dimethylamido)zirconium (TDMAZ, Zr[N(CH.sub.3).sub.2].sub.4), zirconium tetrachloride (ZrCl.sub.4), tetrakis(dimethylamido)tin (TDMASn, Sn[N(C.sub.2H.sub.5).sub.2].sub.4), or the like, and the second precursor gas may include, for example, an oxygen source (e.g., water (H.sub.2O), oxygen (O.sub.2), ozone (O.sub.3), hydrogen peroxide (H.sub.2O.sub.2), nitrous oxide (N.sub.2O), or the like), another reacting compound (e.g., nitrogen (N.sub.2), ammonia (NH.sub.3), or the like), combinations thereof, or the like.

[0086] In FIGS. 20A-20D, a bottom anti-reflective coating (BARC) layer 246 is formed over the hard mask layer 244. The BARC layer 246 serves to reduce reflection during a following lithography exposure process. In some embodiments, the BARC layer 246 may be an organic

BARC layer spin-coated on both the first device region **1001** and the second device region **1002**. If the hard mask layer **244** includes unsealed seam-holes GP in the sheet-sheet spaces **243** as illustrated in FIG. **19C**, BARC materials may inadvertently flow into the seam-holes GP, as illustrated in FIGS. **20C** and **20D**. In a following plasma ashing process for removing the BARC layer **246**, it is difficult to remove BARC materials in the seam-holes GP, which in turn may leave BARC residues in the sheet-sheet spaces, thus impeding following deposition of gate metal materials in the sheet-sheet spaces. In contrast, if the hard mask layer **244** is seam-free as illustrated in FIG. **19A**, no BARC material flows into the sheet-sheet spaces as illustrated in FIG. **20A**, and thus no BARC residue remains in the sheet-sheet spaces after the following plasma ashing process is complete, which in turn facilitates following deposition of gate metal materials in the sheet-sheet spaces.

[0087] In FIGS. **21A** and **21B**, a photoresist layer **248** is then formed over the BARC layer **246** and patterned to expose the second device region **1002** but not expose the first device region **1001**. In some embodiments, the photoresist layer **248** is an organic material formed using a spin-on coating process, followed by patterning the organic material to expose the second device region **1002** using suitable photolithography techniques. For example, photoresist material is irradiated (exposed) and developed to remove portions of the photoresist material. In greater detail, a photomask or reticle (not shown) may be placed above the photoresist material, which may then be exposed to a radiation beam which may be ultraviolet (UV) or an excimer laser such as a Krypton Fluoride (KrF) excimer laser, or an Argon Fluoride (ArF) excimer laser. Exposure of the photoresist material may be performed, for example, using an immersion lithography tool or an extreme ultraviolet light (EUV) tool to increase resolution and decrease the minimum achievable pitch. The BARC layer **246** serves to reduce reflection during the exposure of the photoresist material. A bake or cure operation may be performed to harden the exposed photoresist material, and a developer may be used to remove either the exposed or unexposed portions of the photoresist material depending on whether a positive or negative resist is used.

[0088] After the patterned photoresist layer **248** is formed, the exposed portion of the BARC layer **246** in the second device region **1002** is removed by using the patterned photoresist layer **248** as an etch mask, so that the hard mask layer **244** is exposed in the second device region **1002**. In some embodiments, the hard mask layer **244** may be etched by using a plasma dry etching using fluorine-based and/or chlorine-based etchants.

[0089] Next, in FIGS. **22A** and **22B**, exposed portion of the hard mask layer **244** in the second device region **1002** and the underlying portion of the second gate dielectric layer **242** in the second device region **1002** are removed by using the photoresist layer **248** as an etch mask, so that the first gate dielectric layer is exposed in the second device region. In some embodiments, the hard mask layer **244**, and the second gate dielectric layer **242** may be etched by using a plasma dry etching using fluorine-based and/or chlorine-based etchants. In some embodiments, the BARC layer **246**, the hard mask layer **244**, and the second gate dielectric layer **242** in the second device region **1002** are etched in a continuous plasma etching process using a same etchant. In some other embodiments, two or more of the BARC layer **246**, the hard mask layer **244**, and the second gate dielectric layer **242** in the second device region **1002** are etched in different etching processes using different etchants. For example, the hard mask layer **244** may be removed by a wet etching process using an etchant that is selective to the material of the hard mask layer **244**. Stated differently, the etchant used in removing the hard mask layer **244** etches the material (e.g., aluminum oxide) of the hard mask layer **244** at a faster etch rate than etching the material (e.g., lanthanum oxide) of the second gate dielectric layer **242**. After the hard mask layer **244** removal is complete, the exposed second gate dielectric layer **242** is removed by dry etching or wet etching using an etchant that is selective to the material of the second gate dielectric layer **242**. In this scenario, the etchant used in removing the second gate dielectric layer **242** etches the material (e.g., lanthanum oxide) of the second gate dielectric layer **242** at a faster etch rate than etching the material (e.g., hafnium oxide)

of the first gate dielectric layer **240**, so as to prevent damaging the first gate dielectric layer **240**. [0090] Next, the photoresist layer **248** and the BARC layer **246** are removed from the first device region **1001** by using, for example, a plasma ash process. The resultant structure is illustrated in FIGS. **23A** and **23B**. In some embodiments, a plasma ash process is performed such that the temperature of the organic materials of the photoresist and BARC are increased until these organic materials experience a thermal decomposition and may be removed. The remaining hard mask layer **244** is removed from the first device region **1001** by, for example, a wet etching process using an etchant that is selective to the material of the hard mask layer **244**. Stated differently, the etchant used in removing the hard mask layer **244** from the first device region **1001** etches the material (e.g., aluminum oxide) of the hard mask layer **244** at a faster etch rate than etching the material (e.g., lanthanum oxide) of the second gate dielectric layer **242**.

[0091] In FIGS. **23A** and **23B**, a transistor in the first device region **1001** has a first gate dielectric layer **240** and a second gate dielectric layer **242**, whereas a transistor in the second device region **1002** has a first gate dielectric layer **240** but is free of a second gate dielectric layer **242**. Therefore, the transistor in the first device region **1001** has a different gate dielectric composition than the transistor in the second device region **1002**, which in turn results in threshold voltage difference between the transistor in the first device region **1001** and the transistor in the second device region **1002**.

[0092] In FIGS. **24A** and **24B**, one or more work function metal layers **250** is deposited on the second gate dielectric layer **242** in the first device region **1001**, and on the first gate dielectric layer **240** in the second device region **1002**, followed by depositing a fill metal **252** on the one or more work function metal layers **250** to fill a remainder of gate trenches. A CMP is then performed on the fill metal **252** until the ILD layer **236** is exposed, resulting in the fill metal **252**, the one or more work function metal layers **250**, the first and second gate dielectric layers **240**, **242**, the CESL **234**, and the ILD layer **236** having substantially level top surfaces.

[0093] In some embodiments, a number of work function metal layers **250** in the first device region **1001** is the same as a number of the work function metal layers **250** in the second device region **1002**, if the gate dielectric composition difference achieves a satisfactory threshold voltage tuning result. In some other embodiments, a number of the work function metal layer **250** in the first device region **1001** may be more or fewer than a number of the work function metal layer **250** in the second device region **1002** for further aiding in threshold voltage tuning. Gate stacks having different numbers of work function metal layers **250** may be fabricated using suitable photolithography and etching processes as described previously with respect to FIGS. **18A-22B**. For example, first and second work function metal layers are globally deposited over the first and second device region **1001** and **1002**, and a hard mask layer is then deposited over the second work function metal layer by using the ALD process as described previously with respect to FIGS. **18A-19E**, and the hard mask layer is then patterned to expose a portion of the second work function metal layer in one of the first and second device regions **1001** and **1002**, followed by removing the exposed portion of the second work function metal layer. As a result, a first gate stack in a first one of the first and second device regions **1001** and **1002** has two work function metal layers, and a second gate stack in a second one of the first and second device regions **1001** and **1002** has one work function metal layer.

[0094] The one or more work function metal layers **250** may include one or more work function metals to provide a suitable work function for the high-k/metal gate structures. For an n-type GAA FET, the one or more work function metal layers **250** may include one or more n-type work function metals (N-metal). The n-type work function metals may exemplarily include, but are not limited to, titanium aluminide (TiAl), titanium aluminium nitride (TiAlN), carbo-nitride tantalum (TaCN), hafnium (Hf), zirconium (Zr), titanium (Ti), tantalum (Ta), aluminum (Al), metal carbides (e.g., hafnium carbide (HfC), zirconium carbide (ZrC), titanium carbide (TiC), aluminum carbide (AlC)), aluminides, and/or other suitable materials. On the other hand, for a p-type GAA FET, the

one or more work function metal layers **250** may include one or more p-type work function metals (P-metal). The p-type work function metals may exemplarily include, but are not limited to, titanium nitride (TiN), tungsten nitride (WN), tungsten (W), ruthenium (Ru), palladium (Pd), platinum (Pt), cobalt (Co), nickel (Ni), conductive metal oxides, and/or other suitable materials. [0095] In some embodiments, the fill metal **252** may exemplarily include, but are not limited to, tungsten, aluminum, copper, nickel, cobalt, titanium, tantalum, titanium nitride, tantalum nitride, nickel silicide, cobalt silicide, TaC, TaSiN, TaCN, TiAl, TiAlN, or other suitable materials.

[0096] Based on the above discussions, it can be seen that the present disclosure in various embodiments offers advantages. It is understood, however, that other embodiments may offer additional advantages, and not all advantages are necessarily disclosed herein, and that no particular advantage is required for all embodiments. One advantage is that lengthened pulse time and/or purge time in each ALD cycle of hard mask deposition can reduce a number of seam-holes to an acceptable amount in a resultant hard mask layer or even form a seam-free hard mask layer. Another advantage is that a seam-free hard mask layer can aid in reducing the risk that organic materials (e.g., BARC materials) flow into sheet-sheet spaces between corresponding nanosheets. Another advantage is that a hard mask layer having an acceptable amount of seam-holes may be advantageous for the hard mask removal process.

[0097] In some embodiments, a method comprises forming a first fin and a second fin over a substrate, the first and second fins each comprising alternately stacking first semiconductor layers and second semiconductor layers; forming dummy gate structures over the first and second fins, and gate spacers on either side of the dummy gate structures; removing the dummy gate structures to form a first gate trench over first fin and a second gate trench over the second fin; removing the first semiconductor layers such that the second semiconductor layers are suspended in the first and second gate trenches; depositing a first gate dielectric layer around each of the second semiconductor layers and a second gate dielectric layer around the first gate dielectric layer; performing an atomic layer deposition (ALD) process to form a hard mask layer around the second gate dielectric layer, the ALD process comprising pulsing a first precursor into a deposition chamber for a first pulse time longer than about one second; patterning the hard mask layer; and with the patterned hard mask layer in place, etching a portion of the second gate dielectric layer in the second gate trench. In some embodiments, the ALD process further comprises after pulsing the first precursor into the deposition chamber, pulsing a second precursor into the deposition chamber for a second pulse time longer than about one second. In some embodiments, the first pulse time is substantially the same as the second pulse time. In some embodiments, the first precursor is oxygen-containing, and the second precursor is metal-containing. In some embodiments, the first precursor is oxygen-containing, and the second precursor is aluminum-containing. In some embodiments, the ALD process further comprises after pulsing the first precursor into the deposition chamber and before pulsing the second precursor into the deposition chamber, purging the deposition chamber for a purge time, and the purge time is at least about fifteen times the first pulse time. In some embodiments, the ALD process further comprises after pulsing the second precursor into the deposition chamber, purging the deposition chamber for a purge time, and the purge time is at least about ten times the second pulse time. In some embodiments, the second gate dielectric layer and the hard mask layer are metal oxide layers having different metal compositions. In some embodiments, the second gate dielectric layer comprises lanthanum oxide, and the hard mask layer comprises aluminum oxide. In some embodiments, the first gate dielectric layer comprises hafnium oxide. In some embodiments, the method further comprises after etching the portion of the second gate dielectric layer in the second gate trench, removing the patterned hard mask layer; and after removing the patterned hard mask layer, depositing one or more metal materials in the first and second gate trenches.

[0098] In some embodiments, a method comprises forming first and second fins over a substrate, the first and second fins each comprising alternately stacking first semiconductor layers and second

semiconductor layers; forming first and second dummy gate structures across the first and second fins; forming first gate spacers on either side of the first dummy gate structure and second gate spacers on either side of the second dummy gate structure; removing the first and second dummy gate structures to form a first gate trench between the first gate spacers and a second gate trench between the second gate spacers; selectively etching the first semiconductor layers in the first and second gate trenches; depositing a first gate dielectric layer in the first and second gate trenches and a second gate dielectric layer over the first gate dielectric layer; forming a hard mask layer over the second gate dielectric layer by using one or more atomic layer deposition (ALD) cycles each comprising sequentially performing a first pulse step, a first purge step for a first purge time, a second pulse step, and a second purge step for a second purge time, wherein the first purge time is longer than the second purge time; patterning the hard mask layer to expose a portion of the second gate dielectric layer; and etching the exposed portion of the second gate dielectric layer. In some embodiments, the first pulse step pulses an oxygen-containing precursor for a pulse time shorter than both the first and second purge times. In some embodiments, the first purge time is at least about fifteen times the pulse time. In some embodiments, the second pulse step pulses an aluminum-containing precursor for a pulse time shorter than both the first and second purge times. In some embodiments, the second purge time is at least about ten times the pulse time. In some embodiments, the first pulse step continues for a first pulse time, and the second pulse step continues for a second pulse time, and a ratio of the first purge time to the first pulse time is greater than a ratio of the second purge time to the second pulse time.

[0099] In some embodiments, a method comprises forming a first fin and a second fin, the first and second fins each comprising alternately stacking first semiconductor layers and second semiconductor layers; forming dummy gate structures across the first and second fins, respectively; forming gate spacers on either side of the dummy gate structures; removing the dummy gate structures and the first semiconductor layers to form a plurality of spaces between corresponding ones of the second semiconductor layers; depositing in sequence a first gate dielectric layer and a second gate dielectric layer into the plurality of spaces between corresponding ones of the second semiconductor layers; performing an atomic layer deposition (ALD) process to form a hard mask layer on the second gate dielectric layer, the ALD process comprising pulsing a first precursor into a deposition chamber for a first pulse time, and purging the first precursor from the deposition chamber for a first purge time, the first purge time being at least about fifteen times the first pulse time; patterning the hard mask layer to expose a portion of the second gate dielectric layer; and etching the exposed portion of the second gate dielectric layer. In some embodiments, the first pulse time is greater than about one second. In some embodiments, the ALD process further comprises after purging the first precursor from the deposition chamber, pulsing a second precursor into the deposition chamber for a second pulse time, the second pulse time being greater than about one second.

[0100] The foregoing outlines features of several embodiments so that those skilled in the art may better understand the aspects of the present disclosure. Those skilled in the art should appreciate that they may readily use the present disclosure as a basis for designing or modifying other processes and structures for carrying out the same purposes and/or achieving the same advantages of the embodiments introduced herein. Those skilled in the art should also realize that such equivalent constructions do not depart from the spirit and scope of the present disclosure, and that they may make various changes, substitutions, and alterations herein without departing from the spirit and scope of the present disclosure.

Claims

1. A method, comprising: forming a first channel region and a second channel region over a substrate and extending lengthwise along a first direction; forming a third channel region and a

fourth channel region over the substrate and extending lengthwise along the first direction; forming an isolation feature having a first portion extending laterally between the first channel region and the second channel region, and a second portion extending laterally between the third channel region and the fourth channel region; and forming a first gate structure over the first channel region and interfacing a top surface of the first portion of the isolation feature, and a second gate structure over the second channel region and interfacing a top surface of the second portion of the isolation feature, wherein forming the first and second gate structures comprises: depositing a first gate dielectric layer and a second gate dielectric layer over the first gate dielectric layer; forming a hard mask layer over the second gate dielectric layer by performing at least one atomic layer deposition (ALD) cycle that comprises a pulsing an oxygen-containing precursor and pulsing an aluminum-containing precursor after pulsing the oxygen-containing precursor; patterning the hard mask layer to expose a portion of the second gate dielectric layer; and etching the second gate dielectric layer.

2. The method of claim 1, wherein the ALD cycle further comprises: after pulsing the oxygen-containing precursor and before pulsing the aluminum-containing precursor, performing a first purge step for a first purge duration; and after pulsing the aluminum-containing precursor, performing a second purge step for a second purge duration.
3. The method of claim 2, wherein a ratio of the first purge duration to a duration of pulsing the oxygen-containing precursor is greater than a ratio of the second purge duration to a duration of pulsing the aluminum-containing precursor.
4. The method of claim 2, wherein the first purge duration is greater than the second purge duration.
5. The method of claim 1, wherein a duration of pulsing the oxygen-containing precursor is the same as a duration of pulsing the aluminum-containing precursor.
6. The method of claim 1, wherein a duration of pulsing the oxygen-containing precursor is greater than a value within a range of 0.8 seconds to 1.2 seconds.
7. The method of claim 1, wherein a duration of pulsing the aluminum-containing precursor is greater than a value within a range of 0.8 seconds to 1.2 seconds.
8. The method of claim 1, wherein forming the first and second gate structure further comprises: after etching the second gate dielectric layer, depositing one or more metal layers over the first gate dielectric layer and a remaining portion of the second gate dielectric layer.
9. The method of claim 1, further comprising: forming source/drain features interfacing opposite surfaces of the first channel region.
10. A method, comprising: forming a first semiconductor structure and a second semiconductor structure over a substrate; forming a first isolation feature over the substrate and adjacent to the first semiconductor structure, and a second isolation feature over the substrate and adjacent to the second semiconductor structure; forming a first gate structure over the first semiconductor structure and the first isolation feature, wherein forming the first gate structure comprises forming a first gate dielectric over the first semiconductor structure and at least one titanium-containing metal layer spaced apart from the first semiconductor structure by the first gate dielectric; and forming a second gate structure over the second semiconductor structure and the second isolation feature, wherein forming the second gate structure comprises forming a second gate dielectric over the second semiconductor structure and at least one titanium-containing metal layer spaced apart from the second semiconductor structure by the second gate dielectric, wherein forming the first gate dielectric and the second gate dielectric comprises: depositing a first metal oxide layer and a second metal oxide layer over the first metal oxide layer; forming a hard mask layer over the second metal oxide layer by performing at least one atomic layer deposition (ALD) cycle that comprises a pulsing an oxygen-containing precursor and pulsing a metal-containing precursor, wherein the oxygen-containing precursor is pulsed for a first pulse duration greater than a value within a range of 0.8 seconds to 1.2 seconds; patterning the hard mask layer to expose a portion of the second metal oxide layer above the second semiconductor structure and the second isolation

feature; and removing the exposed portion of the second metal oxide layer.

11. The method of claim 10, wherein the metal-containing precursor is pulsed for a second pulse duration greater than a value within a range of 0.8 seconds to 1.2 seconds.

12. The method of claim 10, wherein the metal-containing precursor is pulsed for a second pulse duration the same as the first pulse duration.

13. The method of claim 10, wherein the ALD cycle further comprises: performing a first purge step between pulsing the oxygen-containing precursor and pulsing the metal-containing precursor; and performing a second purge step after pulsing the metal-containing precursor.

14. The method of claim 13, wherein a duration of the first purge step is greater than a duration of the second purge step.

15. The method of claim 13, wherein a ratio of a duration of the first purge step to a duration of pulsing the oxygen-containing precursor is greater than a ratio of a duration of the second purge step to a duration of pulsing the metal-containing precursor.

16. The method of claim 10, wherein the metal-containing precursor is an aluminum-containing precursor.

17. A method, comprising: forming a first channel region and a second channel region over a substrate and extending lengthwise along a first direction; forming a third channel region and a fourth channel region over the substrate and extending lengthwise along the first direction forming an isolation feature having a first portion extending laterally between the first channel region and the second channel region, and a second portion extending laterally between the third channel region and the fourth channel region; and forming a first gate structure over the first channel region and interfacing a top surface of the first portion of the isolation feature, and a second gate structure over the second channel region and interfacing a top surface of the second portion of the isolation feature, wherein forming the first and second gate structures comprises: depositing a first gate dielectric layer and a second gate dielectric layer over the first gate dielectric layer; forming a hard mask layer over the second gate dielectric layer by performing at least one atomic layer deposition (ALD) cycle that comprises a pulsing an oxygen-containing precursor and pulsing a metal-containing precursor, wherein the metal-containing precursor is pulsed for a first pulse duration greater than a value within a range of 0.8 seconds to 1.2 seconds; patterning the hard mask layer to expose a portion of the second gate dielectric layer; and etching the second gate dielectric layer.

18. The method of claim 17, wherein the oxygen-containing precursor is pulsed for a second pulse duration greater than a value within a range of 0.8 seconds to 1.2 seconds.

19. The method of claim 17, where the ALD cycle further comprises: performing a first purge step after pulsing the oxygen-containing precursor; and performing a second purge step after pulsing the metal-containing precursor.

20. The method of claim 19, wherein a duration of the first purge step is greater than a duration of the second purge step.
