

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12388236
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Barve; Ajit Vijay et al.

Bottom-emitting emitter array with a bottom side metal layer

Abstract

In some implementations, an emitter array may include a substrate, an epitaxial structure on the substrate, a plurality of bottom-emitting emitters defined in the epitaxial structure, a first electrical contact positioned at a top side of the epitaxial structure, a second electrical contact positioned at the top side of the epitaxial structure, and a metal layer disposed on a bottom side of the substrate. The metal layer may be electrically connected to the second electrical contact. The metal layer may include one or more openings for light emission of the plurality of bottom-emitting emitters.

Inventors:	Barve; Ajit Vijay (San Jose, CA), Hegblom; Eric R. (Sunnyvale, CA)
Applicant:	Lumentum Operations LLC (San Jose, CA)
Family ID:	81257179
Assignee:	Lumentum Operations LLC (San Jose, CA)
Appl. No.:	18/423416
Filed:	January 26, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240170927 A1	May. 23, 2024

Related U.S. Application Data

continuation parent-doc US 17247659 20201218 US 11888293 child-doc US 18423416
us-provisional-application US 63198554 20201027

Publication Classification

Int. Cl.: H01S5/42 (20060101); H01S5/042 (20060101); H01S5/183 (20060101)

U.S. Cl.:

CPC **H01S5/423** (20130101); **H01S5/04257** (20190801); **H01S5/18305** (20130101);
H01S5/18361 (20130101); **H01S5/18386** (20130101); **H01S5/18394** (20130101);

Field of Classification Search

CPC: H01S (5/423); H01S (5/04257); H01S (5/18305); H01S (5/18361); H01S (5/18386);
 H01S (5/18394)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
11888293	12/2023	Barve	N/A	H01S 5/04257
2015/0311673	12/2014	Wang et al.	N/A	N/A
2017/0256915	12/2016	Ghosh et al.	N/A	N/A
2018/0198254	12/2017	Tatum et al.	N/A	N/A
2020/0067278	12/2019	Han et al.	N/A	N/A
2022/0131346	12/2021	Barve et al.	N/A	N/A

OTHER PUBLICATIONS

Foresi, J., et al., "VCSEL Arrays for Quasi-Continuous-Wave Applications," Proceedings of SPIE, 2019, vol. 10938, 10 pages. cited by applicant

Primary Examiner: Zhang; Yuanda

Attorney, Agent or Firm: Harrity & Harrity, LLP

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 17/247,659, filed Dec. 18, 2020 (now U.S. Pat. No. 11,888,293), which claims priority to U.S. Provisional Patent Application No. 63/198,554, filed on Oct. 27, 2020, the contents of which are incorporated herein by reference in their entireties.

TECHNICAL FIELD

(1) The present disclosure relates generally to lasers and to a bottom-emitting emitter array with a bottom side metal layer.

BACKGROUND

(2) A vertical-emitting device, such as a vertical cavity surface emitting laser (VCSEL), may include a laser and/or an optical transmitter, among other examples, in which a beam is emitted in a direction perpendicular to a surface of a substrate (e.g., vertically from a surface of a semiconductor wafer). Multiple vertical-emitting devices may be arranged in one or more emitter arrays (e.g., VCSEL arrays) on a common substrate.

SUMMARY

(3) In some implementations, an emitter array includes a substrate; an epitaxial structure on the substrate; a plurality of bottom-emitting emitters defined in the epitaxial structure; a first electrical

contact positioned at a top side of the epitaxial structure; a second electrical contact positioned at the top side of the epitaxial structure; and a metal layer disposed on a bottom side of the substrate, where the metal layer is electrically connected to the second electrical contact, and where the metal layer includes one or more openings for light emission of the plurality of bottom-emitting emitters.

(4) In some implementations, a VCSEL array includes a substrate; an epitaxial structure on the substrate; a plurality of bottom-emitting VCSELs defined in the epitaxial structure; a first electrical contact positioned at a top side of the epitaxial structure; a second electrical contact positioned at the top side of the epitaxial structure; and a metal layer disposed on a bottom side of the substrate, where the metal layer includes one or more openings.

(5) In some implementations, an optical source includes an emitter array that includes a substrate; an epitaxial structure on the substrate, the epitaxial structure including a top mirror and a bottom mirror; a plurality of bottom-emitting emitters defined in the epitaxial structure; a first electrical contact positioned at a top side of the epitaxial structure; a second electrical contact positioned at the top side of the epitaxial structure, where the second electrical contact is laterally distanced from the plurality of bottom-emitting emitters; and a metal layer disposed on a bottom side of the substrate, where the metal layer includes one or more openings for light emission of the plurality of bottom-emitting emitters.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a diagram illustrating an example cross-section of an emitter array described herein.
- (2) FIG. 2 is a diagram illustrating an example cross-section of an emitter array described herein.
- (3) FIG. 3 is a diagram illustrating an example bottom side of the emitter array of FIG. 2.
- (4) FIG. 4 is a diagram illustrating an example bottom side of the emitter array of FIG. 2.

DETAILED DESCRIPTION

- (5) The following detailed description of example implementations refers to the accompanying drawings. The same reference numbers in different drawings may identify the same or similar elements.
- (6) As described above, a vertical-emitting device, such as a vertical cavity surface emitting laser (VCSEL), is a laser in which a beam is emitted in a direction perpendicular to a surface of a substrate (e.g., vertically from a surface of a semiconductor wafer). A VCSEL may be formed in epitaxial layers, of an epitaxial structure, that include one or more active layers (e.g., gain regions). A VCSEL may be a top emitting VCSEL or a backside emitting or bottom emitting (BE) VCSEL. In some cases, a device may employ a single VCSEL, or may employ a plurality of VCSELs arranged in one or more emitter arrays on a common substrate (e.g., on a singlet die or on a single chip).
- (7) Typically, a BE VCSEL array may include a set of electrical contacts on a top side of the VCSEL array. For example, the BE VCSEL array may include an anode contact on the top side of the BE VCSEL array that is situated above the plurality of VCSELs, and a cathode contact on the top side of the BE VCSEL array that is laterally distanced from the plurality of VCSELs. In this configuration, current may flow from the anode, through at least one active region in the epitaxial structure, and into the cathode. Due to the lateral separation between the anode and cathode, carriers must travel a relatively long path for current flow, which adds resistance across the BE VCSEL array. This may result in an optical power gradient across the BE VCSEL array, such that the BE VCSEL array lacks optical power uniformity. For example, VCSELs closer to the cathode may detect higher voltage, resulting in higher bias current per VCSEL, while VCSELs further from the cathode may detect lower voltage, resulting in lower bias current per VCSEL. Thus, in particular detection and sensing applications, where accuracy is dependent upon the uniformity of

the optical power, the BE VCSEL array may be unsuitable or may require additional, complex systems to compensate for the lack of optical power uniformity.

(8) Some implementations described herein provide a BE emitter array (e.g., a BE VCSEL array) with improved optical power uniformity. The emitter array may include an epitaxial structure in which a plurality of BE emitters are formed. The top side of the BE emitter array may include a set of electrical contacts, and the bottom side of the emitter array may include a metal layer. The metal layer may reduce a lateral voltage gradient of the emitter array, thereby reducing an optical power gradient across the emitter array. In this way, the emitter array has improved optical power uniformity without increasing chip size. Accordingly, the emitter array may enable optical detection and sensing to be performed with improved accuracy. In some implementations, an optical source (e.g., for sensing applications) may include the BE emitter array. In some implementations, a method may include generating (or forming) an array of light spots for three-dimensional sensing using the BE emitter array described herein.

(9) FIG. 1 is a diagram illustrating an example cross-section of an emitter array **100** described herein. As shown in FIG. 1, the emitter array **100** may include a substrate **102** and an epitaxial structure **104** (e.g., including a plurality of epitaxial layers). The epitaxial structure **104** may include a bottom mirror **106** and a top mirror **108**. Between the bottom mirror **106** and the top mirror **108**, the epitaxial structure **104** may include one or more additional layers, such as one or more active layers, one or more confinement (e.g., optical confinement) layers, and/or one or more tunnel junction layers. A plurality of emitters may be formed in the epitaxial structure **104**. Reference number **110** shows example positions of the plurality of emitters (which may be referenced herein using reference number **110**) at a surface of the epitaxial structure **104**. The plurality of emitters **110** may extend into the epitaxial structure **104** through one or more layers of the epitaxial structure **104** described herein (e.g., the top mirror **108**, the one or more additional layers, and the bottom mirror **106**). The emitter array **100** also may include a set of electrical contacts **112** (shown as a first electrical contact **112a** and a second electrical contact **112b**). In some implementations, the emitter array **100** may be manufactured using a series of procedures. For example, one or more layers of the emitter array **100** may be created using one or more growth procedures, one or more deposition procedures, one or more etching procedures, one or more oxidation procedures, one or more implantation procedures, and/or one or more metallization procedures, among other examples.

(10) The emitter array **100** shown in FIG. 1 is illustrated as a BE emitter array (e.g., the plurality of emitters **110** are BE emitters that emit light through the substrate **102**). In some implementations, the emitter array **100** is a VCSEL array, and the plurality of emitters **110** are a plurality of VCSELs (e.g., BE VCSELs).

(11) The substrate **102** includes a substrate upon which the epitaxial structure **104** is grown. In some implementations, the substrate **102** may be formed from a semiconductor material, such as gallium arsenide (GaAs), indium phosphide (InP), and/or another type of semiconductor material. In some examples, the substrate **102** may be semi-insulating or N-doped.

(12) The epitaxial structure **104** includes a set of layers grown on the substrate **102**. In some implementations, the epitaxial structure **104** may include a set of aluminum GaAs (AlGaAs) layers grown on the substrate **102** (e.g., a GaAs substrate). In some implementations, the epitaxial structure **104** may be grown on the substrate **102** using a metal-organic chemical vapor deposition (MOCVD) technique and/or a molecular beam epitaxy (MBE) technique, among other examples.

(13) As shown in FIG. 1, the epitaxial structure **104** includes the bottom mirror **106**. The bottom mirror **106** includes a bottom reflector layer of the emitter array **100**. The epitaxial structure **104** also includes the top mirror **108**. The top mirror **108** includes a top reflector layer of the emitter array **100**. The bottom mirror **106** and the top mirror **108** may form an optical resonator of the emitter array **100**. The bottom mirror **106** and/or the top mirror **108** may include a Distributed Bragg Reflector (DBR) and/or a dielectric mirror, among other examples. For example, the bottom

mirror **106** may include an N-DBR layer and the top mirror **108** may include a P-DBR layer.

(14) The epitaxial structure **104** may include one or more active layers (not shown) between the bottom mirror **106** and the top mirror **108**. An active layer may include an active region where electrons and holes recombine to emit light. For example, the active region may include one or more quantum wells. Moreover, the epitaxial structure **104** may include one or more confinement layers (not shown) that provide (e.g., via an aperture) optical and/or electrical confinement. For example, the epitaxial structure **104** may include one or more oxidation layers. An oxidation layer may be formed as a result of oxidation of one or more epitaxial layers of the epitaxial structure **104**. For example, an oxidation layer may be an aluminum oxide (Al₂O₃) layer formed as a result of oxidation of an epitaxial layer (e.g., an AlGaAs layer and/or an aluminum arsenide (AlAs) layer, among other examples). In addition, the epitaxial structure **104** may include one or more tunnel junctions (not shown) (e.g., between active layers) that provide conduction of carriers so that the carriers can be used for additional stimulated recombination events. A tunnel junction may be formed of layers (e.g., thin layers) of highly-doped semiconductor materials (e.g., one or more N⁺⁺ layers and one or more P⁺⁺ layers).

(15) The emitter array **100** may include the first electrical contact **112a** and the second electrical contact **112b** to enable electrical current to flow through the emitter array **100**. The first electrical contact **112a** and the second electrical contact **112b** may be metal contacts, such as ohmic metal contacts. In some implementations, the first electrical contact **112a** is a P-metal contact, and the second electrical contact **112b** is an N-metal contact. For example, the first electrical contact **112a** may be an anode contact and the second electrical contact **112b** may be a cathode contact. In some implementations, the first electrical contact **112a** and the second electrical contact **112b** may both be N-metal contacts (or P-metal contacts), and the epitaxial structure **104** may include one or more tunnel junctions. In some implementations, the first electrical contact **112a** and/or the second electrical contact **112b** may include an annealed metallization layer. For example, the first electrical contact **112a** and/or the second electrical contact **112b** may include a chromium-gold (Cr—Au) layer, gold-zinc (Au—Zn), or a titanium-platinum-gold (TiPtAu) layer, among other examples, through which electrical current may flow.

(16) The first electrical contact **112a** may be positioned at the top side (e.g., the front side) of the emitter array **100** (e.g., opposite the substrate **102** and adjacent the epitaxial structure **104**). The position of the first electrical contact **112a** may define the location of the plurality of emitters **110** in the epitaxial structure **104** (e.g., the first electrical contact **112a** may vertically align with the plurality of emitters **110**). The second electrical contact **112b** also may be positioned at the top side of the emitter array **100**. The second electrical contact **112b** may be laterally distanced from the plurality of emitters **110** (e.g., the second electrical contact **112b** may not vertically align with the plurality of emitters **110**). The second electrical contact **112b** may fill a trench that extends to the bottom mirror **106** (e.g., the N-DBR layer), the substrate **102**, or a separate contact layer (e.g., a separate N-doped contact layer). The first electrical contact **112a** and the second electrical contact **112b** may be electrically separated from each other.

(17) The second electrical contact **112b** may be electrically connected to the bottom mirror **106** (e.g., the N-DBR layer) and/or the substrate **102**. Thus, current may flow (as shown by current path **114**) from the first electrical contact **112a** (e.g., the P-metal contact), through an active region, the bottom mirror **106** (e.g., the N-DBR layer), and/or one or more N-doped layers, and into the second electrical contact **112b** (e.g., the N-metal contact). If the second electrical contact **112b** is electrically connected to the substrate **102** (e.g., the substrate **102** is N-substrate), current can also flow laterally through the substrate **102** (as shown by current path **116**). Accordingly, as described above, because carriers must travel a relatively long path between the first electrical contact **112a** and the second electrical contact **112b**, resistance is added across the emitter array **100** resulting in an optical power gradient.

(18) The emitter array **100** in FIG. 1 is shown in a planar configuration (e.g., with oxidation

trenches). In some implementations, the emitter array **100** may have an oxide-confined configuration, an implant-only configuration (e.g., for current confinement), or a non-planar configuration, such as a mesa configuration. In the mesa configuration, oxidation trenches are not etched in the epitaxial structure **104**. Rather, areas of the epitaxial structure **104** are etched to leave a respective mesa for each emitter **110**.

(19) In some implementations, the emitter array **100** is configured for wirebond-free attachment to another substrate, such as a sub-mount and/or a printed circuit board, among other examples. For example, the emitter array **100** may be configured for flip-chip bonding (e.g., the emitter array **100** does not include an electrical contact on the bottom side of the emitter array **100**, adjacent the substrate **102**).

(20) In some implementations, the emitter array **100** may be manufactured using a series of steps. For example, the bottom mirror **106**, an active layer, an oxidation layer, and the top mirror **108** may be epitaxially grown on the substrate **102**, after which the first electrical contact **112a** (e.g., the P-metal contact) may be deposited on the top mirror **108**. Next, oxidation trenches may be etched to expose the oxidation layer for oxidation. The second electrical contact **112b** (e.g., the N-metal contact) may be deposited in an oxidation trench and on the top mirror **108**. In some implementations, an implant isolation material may be created via ion implantation, after which a dielectric passivation/mirror layer may be deposited. In some implementations, dielectric via openings may be etched in the dielectric passivation/mirror layer (e.g., to expose the P-metal contact). Plating, seeding, and etching may be performed, after which the substrate **102** may be thinned and/or lapped to a target thickness.

(21) The quantity and arrangement of layers shown in FIG. **1** are provided as an example. In practice, the emitter array **100** may include additional layers, fewer layers, different layers, or differently arranged layers than those shown in FIG. **1**. Additionally, or alternatively, a set of layers (e.g., one or more layers) of the emitter array **100** may perform one or more functions described as being performed by another set of layers of the emitter array **100**, respectively.

(22) While the design of the emitter array **100** is described as including a plurality of VCSELs, other implementations are possible. For example, the design of the emitter array **100** may apply in the context of another type of optical device, such as a light emitting diode (LED), or another type of vertical emitting (e.g., bottom emitting) optical device. Additionally, the design of the emitter array **100** may apply to emitters of any wavelength, power level, emission profile, or the like. In other words, the emitter array **100** is not particular to an emitter with a given performance characteristic. In some implementations, the emitters **110** may output at wavelengths between 900 nanometers (nm) to 1550 nm.

(23) FIG. **2** is a diagram illustrating an example cross-section of an emitter array **200** described herein. As shown in FIG. **2**, the emitter array **200** may have a similar structure to the emitter array **100**. That is, the emitter array **200** may include the substrate **102**, the epitaxial structure **104**, the plurality of emitters **110**, and the set of electrical contacts **112**, as described above. In addition, the emitter array **200** may include a metal layer **202**. The metal layer **202** may be disposed on the bottom side (e.g., the back side) of the emitter array **200** (e.g., opposite the epitaxial structure **104** and adjacent the substrate **102**). The metal layer **202** may include one or more openings **204**. The one or more openings **204** may be configured to pass light emission from the plurality of emitters **110** as shown by the vertical line and downward arrow.

(24) The metal layer **202** may include a conductive layer through which current can flow. For example, the metal layer **202** may include an ohmic metal layer. In some implementations, the metal layer **202** may be composed of the same material as the electrical contacts **112a** and **112b** (e.g., Cr—Au, Au—Zn, or TiPtAu, among other examples). The metal layer **202** may have an electrical connection to the second electrical contact **112b**, the bottom mirror **106**, and/or the substrate **102**. For example, the second electrical contact may include an N-metal contact, the bottom mirror **106** may include an N-DBR layer, and the substrate may include an N-substrate, as

described above, and the metal layer **202** may include an N-metal layer. In this way, current can flow laterally across the metal layer **202** (shown by current path **206**). Moreover, current can flow across the metal layer **202** with less resistance relative to the bottom mirror **106** or the substrate **102**, thereby reducing an optical power gradient across the emitter array **200**.

(25) In some implementations, the substrate **102** may include integrated optics. For example, the bottom of the substrate **102** (e.g., opposite the epitaxial structure **104**) may be formed into one or more optical components, such as one or more lenses, diffusers, and/or diffractive optical elements, among other examples. Here, one or more optical components may align with an opening **204** (e.g., such that vertical light emission of one or more emitters **110** passes through the one or more optical components before passing through the opening **204**).

(26) In some implementations, the polarity of the emitter array **200** may be reversed from the description described herein. For example, the first electrical contact **112a** may include an N-metal contact, the second electrical contact **112b** may include a P-metal contact, the bottom mirror **106** may include a P-DBR layer, the substrate may include a P-substrate, and the metal layer **202** may include a P-metal layer.

(27) As indicated above, FIG. 2 is provided as an example. Other examples may differ from what is described with regard to FIG. 2.

(28) FIG. 3 is a diagram illustrating an example bottom side of the emitter array **200** of FIG. 2. In particular, FIG. 3 shows a bottom view of an example metal layer **202**. As shown, the metal layer **202** may include respective openings **204** for the plurality of emitters **110**. Here, an emission area **302** (e.g., an active area) of each emitter **110** may align with a respective opening **204** in the metal layer **202** (e.g., such that a vertical light emission of the emitter **110** passes through the opening **204**). The metal traces of the metal layer **202** between the respective openings **204** for the emitters **110** provide lateral current transport (shown by current path **206**), which reduces resistance and an optical power gradient across the emitter array **200**.

(29) The openings **204** may be hexagonal, as shown, or may be another shape such as rectangular or circular. The openings **204** may be uniformly or non-uniformly distributed across the metal layer **202** to accommodate uniformly or non-uniformly distributed emitters **110** in the emitter array **200**, respectively.

(30) The openings **204** may have a width (e.g., a smallest dimension) that allows for minimal light blocking that may result from process misalignment and/or light divergence within the substrate **102**. For example, alignment error may be from about 1 to 5 micrometers (μm), and divergence within the substrate **102** may be from about 5 to 10 μm . Accordingly, the openings **204** may have a width that is 10 μm or 20 μm wider than the width of an emission area **302** of an emitter **110**. For example, the openings **204** may have a width of about 30 μm in connection with emitters **110** that have an emission area **302** that is 10 μm wide. Moreover, the spacing between adjacent openings **204** (e.g., between center points of adjacent openings **204**) may be based on the width of the openings **204** and/or an alignment error associated with the application of an anti-reflection (AR) coating and/or the metal layer **202**. For example, a minimum distance between adjacent openings **204** may be about 40 μm in connection with emitters **110** that have an emission area **302** that is 10 μm wide. Stated differently, a minimum distance between adjacent emitters **110** (e.g., between center points of emission areas **302** of adjacent emitters **110**), that have 10 μm emission areas **302**, may be about 40 μm .

(31) In some implementations, AR coating may be applied to the bottom side of the substrate **102**. For example, AR coating may be disposed on the bottom side of the substrate **102** in alignment with each of the respective openings **204**. As an example, AR coating may be disposed in each of the respective openings **204** (e.g., rather than the AR coating being applied as a layer). In some implementations, the emitter array **200** may be configured for use with copper (Cu) pillars. Copper pillars may include a metal post attached by solder to a die and a package substrate, and may provide heat sink and/or electrical conductivity properties. Thus, copper pillars may provide flip-

chip interconnection of the emitter array **200** to another substrate, as described above. Here, respective copper pillars may be connected to the emitter array **200** in alignment with each of the plurality of emitters **110**.

(32) As indicated above, FIG. **3** is provided as an example. Other examples may differ from what is described with regard to FIG. **3**.

(33) FIG. **4** is a diagram illustrating an example bottom side of the emitter array **200** of FIG. **2**. In particular, FIG. **4** shows a bottom view of an example metal layer **202**. As shown, the metal layer **202** may include respective openings **204** for emitter subarrays **402** (or “groups”) of the plurality of emitters **110**. An emitter subarray **402** may include multiple emitters of the plurality of emitters **110**, and each emitter subarray **402** may include different emitters of the plurality of emitters **110**. Here, emission areas **302** of multiple emitters **110** may align with a respective opening **204** in the metal layer **202** (e.g., such that vertical light emissions of the multiple emitters **110** pass through the opening **204**). The metal traces of the metal layer **202** between the respective openings **204** for the emitter subarrays **402** provide lateral current transport, which reduces resistance and an optical power gradient across the emitter array **200**.

(34) An emitter subarray **402** may be arranged in a column of emitters **110**, a row of emitters **110**, and/or a cluster of emitters **110**, among other examples. Accordingly, the openings **204** may be configured for columns of emitters **110** and/or rows of emitters (e.g., elongated openings that run from front-to-back of the metal layer **202** and/or from side-to-side of the metal layer **202**) and/or configured for clusters of emitters **110** (e.g., circular openings, square openings, and/or hexagonal openings, among other examples). In some implementations, a first emitter subarray **402** and a second emitter subarray **402** may have different arrangements (e.g., the first emitter subarray **402** may be arranged in a column and the second emitter subarray **402** may be arranged in a cluster) and/or may include different quantities of emitters **110**. Accordingly, a first opening **204** and a second opening **204** may have different shapes (e.g., to accommodate different arrangements of emitter subarrays **402**) and/or different sizes (e.g., to accommodate different quantities of emitters **110**). The openings **204** may be uniformly or non-uniformly distributed across the metal layer **202** to accommodate uniformly or non-uniformly distributed emitter subarrays **402** in the emitter array **200**, respectively.

(35) In some implementations, different sets of adjacent openings **204** may have different opening-to-opening spacings (e.g., a minimum distance between edges of openings). For example, a first minimum distance between adjacent edges of a first opening **204** and a second opening **204** may be different from a second minimum distance between adjacent edges of a third opening **204** and a fourth opening **204**. In the multiple-group configuration of FIG. **4**, adjacent emitters **110** may be closer together than the emitters **110** in the configuration of FIG. **3**. For example, a minimum distance between adjacent emitters **110** (e.g., between center points of emission areas **302** of adjacent emitters **110**), that have 10 μm emission areas **302**, may be about 18 μm .

(36) In some implementations, AR coating may be disposed on the bottom side of the substrate **102** in alignment with each of the respective openings **204**, as described above. In the multiple-group configuration of FIG. **4**, alignment error associated with the AR coating may be reduced relative to the configuration of FIG. **3** due to the use of larger openings **204** in the multiple-group configuration. In addition, the multiple-group configuration, which uses relatively larger openings **204**, may facilitate integration of optical components on the substrate **102**, as described above. Moreover, in the multiple-group configuration, respective copper pillar blocks may be connected to the emitter array **200** in alignment with each of the openings **204** (e.g., rather than each emitter **110** individually), thereby facilitating use of copper pillar technology.

(37) As indicated above, FIG. **4** is provided as an example. Other examples may differ from what is described with regard to FIG. **4**.

(38) The foregoing disclosure provides illustration and description but is not intended to be exhaustive or to limit the implementations to the precise forms disclosed. Modifications and

variations may be made in light of the above disclosure or may be acquired from practice of the implementations. Furthermore, any of the implementations described herein may be combined unless the foregoing disclosure expressly provides a reason that one or more implementations may not be combined.

(39) Even though particular combinations of features are recited in the claims and/or disclosed in the specification, these combinations are not intended to limit the disclosure of various implementations. In fact, many of these features may be combined in ways not specifically recited in the claims and/or disclosed in the specification. Although each dependent claim listed below may directly depend on only one claim, the disclosure of various implementations includes each dependent claim in combination with every other claim in the claim set. As used herein, a phrase referring to “at least one of” a list of items refers to any combination of those items, including single members. As an example, “at least one of: a, b, or c” is intended to cover a, b, c, a-b, a-c, b-c, and a-b-c, as well as any combination with multiple of the same item.

(40) No element, act, or instruction used herein should be construed as critical or essential unless explicitly described as such. Also, as used herein, the articles “a” and “an” are intended to include one or more items and may be used interchangeably with “one or more.” Further, as used herein, the article “the” is intended to include one or more items referenced in connection with the article “the” and may be used interchangeably with “the one or more.” Furthermore, as used herein, the term “set” is intended to include one or more items (e.g., related items, unrelated items, or a combination of related and unrelated items), and may be used interchangeably with “one or more.” Where only one item is intended, the phrase “only one” or similar language is used. Also, as used herein, the terms “has,” “have,” “having,” or the like are intended to be open-ended terms. Further, the phrase “based on” is intended to mean “based, at least in part, on” unless explicitly stated otherwise. Also, as used herein, the term “or” is intended to be inclusive when used in a series and may be used interchangeably with “and/or,” unless explicitly stated otherwise (e.g., if used in combination with “either” or “only one of”). Further, spatially relative terms, such as “below,” “lower,” “above,” “upper,” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the apparatus, device, and/or element in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

Claims

1. An emitter array, comprising: a substrate; an epitaxial structure on the substrate; a plurality of bottom-emitting emitters defined in the epitaxial structure; a first electrical contact positioned at a top side of the epitaxial structure; a second electrical contact positioned at the top side of the epitaxial structure; and a metal layer disposed on a bottom side of the substrate, wherein the metal layer is electrically connected to the second electrical contact, wherein the metal layer includes openings for the plurality of bottom-emitting emitters, and wherein an emission area of each single bottom-emitting emitter, of the plurality of bottom-emitting emitters, aligns with a single respective opening of the openings.
2. The emitter array of claim 1, wherein the metal layer is configured to have a current path for a current, from the first electrical contact, to flow laterally across the metal layer and into the second electrical contact.
3. The emitter array of claim 1, wherein the metal layer is configured to have a current path for a current, from a bottom-emitting emitter of the plurality of bottom-emitting emitters, to flow laterally across the metal layer and into the second electrical contact.
4. The emitter array of claim 1, wherein each opening, of the openings, is configured to pass

through a vertical light emission from a respective emitter of the plurality of bottom-emitting emitters.

5. The emitter array of claim 1, wherein metal traces of the metal layer between the openings are configured to provide lateral current transport.

6. The emitter array of claim 1, wherein the openings are hexagonal.

7. A vertical-cavity surface-emitting laser (VCSEL) array, comprising: a substrate; an epitaxial structure on the substrate; a plurality of bottom-emitting VCSELs defined in the epitaxial structure; a first electrical contact positioned at a top side of the epitaxial structure; a second electrical contact positioned at the top side of the epitaxial structure; and a metal layer disposed on a bottom side of the substrate, wherein the metal layer is electrically connected to the second electrical contact, wherein the metal layer includes openings for the plurality of bottom-emitting VCSELs, and wherein each single opening, of the openings, aligns with an emission area of a single respective bottom-emitting VCSEL of the plurality of bottom-emitting VCSELs.

8. The VCSEL array of claim 7, wherein the openings are uniformly distributed across the metal layer.

9. The VCSEL array of claim 7, wherein the openings are non-uniformly distributed across the metal layer.

10. The VCSEL array of claim 7, wherein the openings are hexagonal, rectangular, or circular.

11. The VCSEL array of claim 7, wherein the metal layer is configured to have a current path for a current, from the first electrical contact, to flow laterally across the metal layer and into the second electrical contact.

12. The VCSEL array of claim 7, wherein the metal layer is configured to have a current path for a current, from a bottom-emitting VCSEL of the plurality of bottom-emitting VCSELs, to flow laterally across the metal layer and into the second electrical contact.

13. The VCSEL array of claim 7, wherein metal traces of the metal layer between the openings are configured to provide lateral current transport.

14. The VCSEL array of claim 7, wherein each single opening, of the openings, is configured to pass through a vertical light emission from the single respective bottom-emitting VCSEL.

15. An optical source, comprising: an emitter array that comprises: a substrate; an epitaxial structure on the substrate, the epitaxial structure including a top mirror and a bottom mirror; a plurality of bottom-emitting emitters defined in the epitaxial structure; a first electrical contact positioned at a top side of the epitaxial structure; a second electrical contact positioned at the top side of the epitaxial structure, wherein the second electrical contact is laterally distanced from the plurality of bottom-emitting emitters; and a metal layer disposed on a bottom side of the substrate, wherein the metal layer is electrically connected to the substrate, the bottom mirror, and the second electrical contact, wherein the metal layer includes openings for the plurality of bottom-emitting emitters, and wherein an emission area of each single bottom-emitting emitter, of the plurality of bottom-emitting emitters, aligns with a single respective opening of the openings.

16. The optical source of claim 15, wherein the first electrical contact is an anode contact and the second electrical contact is a cathode contact.

17. The optical source of claim 15, wherein the first electrical contact is a P-metal contact and the second electrical contact is an N-metal contact.

18. The optical source of claim 15, wherein the first electrical contact is vertically aligned with the plurality of bottom-emitting emitters.

19. The optical source of claim 15, wherein the metal layer is configured to have a current path for a current, from the first electrical contact, to flow laterally across the metal layer and into the second electrical contact.

20. The optical source of claim 15, wherein the metal layer is configured to have a current path for a current, from a bottom-emitting emitter of the plurality of bottom-emitting emitters, to flow laterally across the metal layer and into the second electrical contact.

