

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250277879

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

Ou; Wei-Lin et al.

Changing Samples in a Magnetic Resonance System

Abstract

In a general aspect, a sample holder has multiple sample containers. In some instances, the sample holder can be received into a resonator package in a primary magnetic field of a magnetic resonance system. The resonator package includes a resonator configured to interact with a sample in a sample region. The sample holder includes a first sample and a calibration sample. The position of the sample holder relative to the resonator is calibrated. After calibrating the position of the sample holder, the sample holder is translated to position the first sample in the sample region. Magnetic resonance data is acquired based on magnetic resonance signals generated by an interaction between the resonator and the first sample.

Inventors: Ou; Wei-Lin (Burlington, CA), Borneman; Troy W. (Waterloo, CA), Thompson; Derek Blair Poirier (Waterloo, CA), Mohebbi; Hamidreza (Waterloo, CA), Boorn; Andrew (Waterloo, CA), Carkner; Donald Edward (Waterloo, CA)

Applicant: Quantum Valley Investment Fund LP (Waterloo, CA)

Family ID: 87748063

Assignee: Quantum Valley Investment Fund LP (Waterloo, CA)

Appl. No.: 19/050450

Filed: February 11, 2025

Related U.S. Application Data

parent WO continuation PCT/CA2023/051098 20230818 PENDING child US 19050450

us-provisional-application US 63399455 20220819

us-provisional-application US 63494161 20230404

Publication Classification

Int. Cl.: G01R33/30 (20060101); G01R33/31 (20060101)

U.S. Cl.:

CPC G01R33/307 (20130101); G01R33/31 (20130101);

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application claims priority to U.S. Provisional Patent Application No. 63/399,455, filed on Aug. 19, 2022 and U.S. Provisional Patent Application No. 63/494,161, filed on Apr. 4, 2023. U.S. Provisional Patent Application No. 63/399,455, filed on Aug. 19, 2022 and U.S. Provisional Patent Application No. 63/494,161 are each incorporated by reference in their entirety.

BACKGROUND

[0002] The following description relates to changing samples in magnetic resonance systems.

[0003] Magnetic resonance systems are used to study various types of samples and phenomena. A resonator manipulates the spins in a sample by producing a magnetic field at or near the spins' resonance frequencies. In some cases, the resonator detects the spins based on a voltage induced by the precessing spins.

Description

DESCRIPTION OF DRAWINGS

[0004] FIG. 1 is a schematic diagram of an example magnetic resonance system.

[0005] FIG. 2 is a perspective view of an example probe for use in a magnetic resonance system.

[0006] FIG. 3 is a perspective view of an example probeless magnetic resonance package.

[0007] FIG. 4 is a perspective view of an example resonator package.

[0008] FIG. 5 is a plan view of an interior of an example resonator package illustrating an example sample holder and an example resonator.

[0009] FIGS. 6A-6B are perspective views of an example resonator illustrating positioning of a sample holder relative thereto.

[0010] FIG. 7 is a cross-sectional view of an example resonator and an example sample holder.

[0011] FIG. 8 is a detailed cross-sectional view of an example resonator package showing an example positioning guide.

[0012] FIGS. 9A is a side view of an example sample holder.

[0013] FIG. 9B is a perspective view of the sample holder of FIG. 9A.

[0014] FIG. 9C is a top view of the sample holder of FIG. 9A.

[0015] FIG. 9D is an end view of the sample holder of FIG. 9A.

[0016] FIG. 10A is a perspective view illustrating attachment of an example sample holder to a transfer arm.

[0017] FIG. 10B is a perspective view illustrating attachment of an example tubular sample holder to a transfer arm.

[0018] FIG. 11A is a flow diagram illustrating an example process for changing samples in a magnetic resonance system using a calibration sample.

[0019] FIG. 11B is a flow diagram illustrating an example process for changing samples in a magnetic resonance system using frequency-shift calibration.

[0020] FIG. 11C is an example plot of sample holder position versus frequency shift.

[0021] FIG. 11D is an example plot which illustrates the resonant frequency shift induced by

sample holders containing samples with differing dielectric constants.

[0022] FIG. 12A is a front view of an example sample holder illustrating sample containers with entry ports.

[0023] FIG. 12B is a detailed front view of the example sample holder of FIG. 12A.

[0024] FIG. 13A is a side view of the example sample holder of FIG. 12A.

[0025] FIG. 13B is a detailed side view of the example sample holder of FIG. 12A.

[0026] FIG. 14A is a front view of an example sample holder illustrating sample containers with offset entry ports and an adhesive channel.

[0027] FIG. 14B is a front view of an example sample holder illustrating sample containers with multiple entry ports and an adhesive channel.

[0028] FIG. 14C is a front view of an example sample holder illustrating laser weld paths.

[0029] FIG. 14D is a front view of the example sample holder including an adhesive channel and laser welds.

[0030] FIG. 15 is an exploded view of an example three-layer sample holder.

DETAILED DESCRIPTION

[0031] In some aspects of what is described, a magnetic resonance system includes a sample changer apparatus that can be used for changing samples. The sample changer apparatus may include a sample holder that holds multiple magnetic resonance samples. The sample holder can be a cartridge, a tubular device, cylindrical or another type of structure that has multiple sample containers. The sample changer apparatus may include additional components that operate to move the sample changer to a selected position relative to a resonator of the magnetic resonance position; for example, the sample changer apparatus may include a sample transfer device, an actuator, a control system, or a combination of these and other components. In some instances, the sample changer apparatus moves the sample holder from an external environment into a controlled environment near the resonator in the primary magnetic field of the magnetic resonance system. As such, in systems that operate at cryogenic temperatures, multiple samples can be moved together from a room temperature and pressure environment into low temperature and pressure environment, so that the samples can be cooled as a group in the controlled environment near the resonator. The sample holder can then be adjusted within the controlled environment to position any one of the samples in the sample region of the resonator. Accordingly, each of the samples can be selected and independently with no interference on their response of each other measured by the magnetic resonance system without having to remove the sample holder from the controlled environment. This can improve sample throughput of the magnetic resonance system, among other advantages.

[0032] In some implementations, one or more of the samples in the sample holder is a calibration sample. The calibration sample can be used to calibrate the position of the sample holder relative to the resonator in the controlled environment of the magnetic resonance system. For instance, the sample changer apparatus may initially position the calibration sample in the sample region of the resonator (e.g., in or adjacent to the resonator, in the magnetic control field generated by the resonator, in a region where the resonator can magnetically control spins in the calibration sample), and the sample changer apparatus may iteratively adjust the position of the sample holder relative to the resonator. In such an iterative process, the magnetic resonance system can move the sample holder through a series of test positions and acquire magnetic resonance data from the calibration sample at each of the test positions. The magnetic resonance data can be analyzed to determine a fiducial reference position for the sample holder. The fiducial reference position can be, for example, the test position where an optimal magnetic resonance signal is obtained from the calibration sample. The reference position can then be used as a datum when the sample changer apparatus subsequently moves any of the other samples into the sample region for analysis. Because each of the samples in the sample holder resides at a known location relative to the calibration sample, determining the ideal position for the calibration sample within the sample

region allows each of the samples to then be precisely positioned at the ideal position for analysis. In some cases, the calibration sample can be used for other purposes, for example, to monitor system performance, etc. The calibration sample can differ from the actual sample under test and is typically chosen from materials with a well-known ESR response, such as PTM, BDPA, etc. The size of the calibration container can be also different from that of the actual sample container.

[0033] Aspects of the systems and techniques described here can be implemented in various types of magnetic resonance systems. For example, a sample changer apparatus may be implemented in a nuclear magnetic resonance (“NMR”) system, an electron spin resonance (“ESR”) or electron paramagnetic resonance (“EPR”) system, an optically detected magnetic resonance (“ODMR”), or another type of magnetic resonance system. As another example, all or part of a sample changer apparatus may be deployed on a probe for a magnetic resonance system, or a sample changer apparatus can be deployed in a probeless magnetic resonance system. In some cases, a sample holder can be adapted to hold liquid samples, solid samples, liquid crystal samples, spin-labeled protein samples, other biological samples (e.g., blood samples, urine samples, saliva samples, etc.), or other types of samples to be measured or otherwise analyzed by a magnetic resonance system. As another example, a sample changer apparatus may be deployed with a resonator package that operates in a cryogenic environment (e.g., at 77 K, 4 K, milliKelvin, or other cryogenic temperatures below 273 K), or a sample changer apparatus may be deployed with a resonator package that operates at non-cryogenic temperatures including room temperatures. The resonator can be, for example, planar resonators (2D) such as a microstrip, coplanar waveguide, split ring, planar lumped element resonators or 3D resonators such as rectangular cavities, cylindrical cavities, birdcage, loop gap, bulk lumped element, a coil, another type of resonator for magnetic resonance systems, or a combination of the above. Additionally, the resonator could be, for example, a rectangular cavity resonator, a cylindrical cavity resonator, a dielectric resonator, a loop gap resonator, or any lumped element resonator.

[0034] In some cases, the systems and techniques presented here can be deployed in connection with various cryogenic systems, including, for example, compact closed-cycle systems, open-cycle, liquid cryogen systems and others. In some cases, the systems and techniques presented here can be deployed in connection with various probes, including compact probe designs that may enable low-noise cryogenic receiver amplifiers to be used in a variety of configurations. In some cases, the techniques and system described here can be deployed in connection with continuous wave (CW) magnetic resonance (e.g., using CW ESR spectroscopy or CW NMR spectroscopy methodology), pulse magnetic resonance (e.g., using pulsed ESR spectroscopy or pulsed NMR spectroscopy methodology), or a combination of these and other MR regimes.

[0035] In some implementations, the systems and techniques described here can provide technical advantages and improvement over existing technologies. As an example, the systems and techniques here may improve system efficiency, for instance, by reducing the amount of time that is required to change samples in a magnetic resonance system. As another example, the systems and techniques here may improve the quality of magnetic resonance data and measurements obtained by a magnetic resonance system, for instance, by allowing precise positioning of samples in the controlled operating environment of the resonator package. Moreover, conducting measurements on various samples within a single setup, utilizing the same resonator magnetic field (also known as the “B1 field”) and consistent conditions, ensures a level of uniformity and precision crucial for meaningful comparisons. Other improvements and advantages may be achieved in some cases.

[0036] Aspects of the systems and techniques described here can be adapted for various types of applications. For example, the systems and techniques described here may be used for structural biology measurements, for instance, to measure structural properties of proteins or protein complexes in a biological sample (e.g., a blood sample, a urine sample, or another type of biological sample). Such measurements can be useful in clinical applications (e.g., diagnostics, treatments, etc.), pharmaceutical drug discovery/development and understanding the structure and

function of membrane proteins, and other applications.

[0037] FIG. 1 is a schematic diagram of an example magnetic resonance system **100**. In various implementations the magnetic resonance system **100** may be utilized, for example, in nuclear magnetic resonance (“NMR”) spectroscopy, electron spin resonance (“ESR”) or electron paramagnetic resonance (“EPR”) spectroscopy, nuclear quadrupole resonance spectroscopy (“NQR”), magnetic resonance imaging (“MRI”), or other applications. The magnetic resonance system **100** includes a sample holder **102** that includes a plurality of sample containers **104**. In various implementations, the sample holder **102** is constructed from a material that has favorable dielectric properties (e.g., low tangent loss) and that is suitable for cryogenic temperatures. In various implementations, the sample holder **102** may be constructed, for example, of quartz, sapphire, borosilicate glass, or other similar material. In the example shown in FIG. 1, the sample holder **102** is coupled to a first end of a sample transfer device **106** via an attachment mechanism **108**. The sample transfer device **106** can move the sample holder **102** and position the sample holder **102** relative to a resonator **110** in the primary magnetic field of the magnetic resonance system **100**. In various implementations, the resonator **110** may be enclosed in a resonator housing or another type of resonator package.

[0038] In the example shown in FIG. 1, a second end of the sample transfer device **106** is coupled to an actuator **112**. In operation, the actuator **112** drives movement of the sample transfer device **106** and may, in various implementations be, for example, a single-degree-of-freedom linear actuator that translates the sample transfer device **106** in a linear fashion along an axis of the sample transfer device **106**. Examples of single-degree-of-freedom linear actuators include, for example, a mechanical linear actuator, an electro-mechanical linear actuator, a linear motor, a piezoelectric actuator, a twisted and coiled polymer (“TCP”) actuator, a hydraulic actuator, a pneumatic actuator, or other type of linear actuator. In various implementations, the actuator **112** could be for example, a multi-degree-of-freedom actuator such as, for example a two-degree-of-freedom actuator that moves the sample transfer device **106** in a linear fashion along two independent (e.g., perpendicular) axes. Such a two-degree-of-freedom linear actuator may, in various implementations, move the sample holder **102** along a first axis relative to the resonator **110** as well as along a second axis thereby adjusting the position of the sample holder **102** relative to the resonator **110** along the second axis. In other implementations, the actuator **112** could be, for example a three-degree-of-freedom actuator that moves the sample transfer device **106** along two linear axes and rotates the sample transfer device **106** about an axis of the sample transfer device **106**. The actuator is coupled to a position control system **115** that controls operation of the actuator. In various implementations, the position control system **115** may be, for example, an automated control system such as, for example, a CNC control system, a PID control system, or other type of controller. In some cases, the position control system **115** may include, or may be implemented as, software or firmware running on a computer system (e.g., a microprocessor or another type of data processing apparatus). In some instances, the control mechanism may be a manual control such as, for example, a caliper, micrometer or hand crank. This can be further enhanced by incorporating a laser indicator.

[0039] In the example shown in FIG. 1, the resonator **110**, the sample holder **102**, the attachment mechanism **108**, and the first end of the sample transfer device **106** are disposed in a controlled environment that is cooled by the cooling system **114**, while the second end of the of the sample transfer device **106** is disposed outside controlled environment. The sample transfer device **106** is introduced to the cooling system **114** via an insertion point **113**. In various embodiments, the insertion point **113** can be or include a valve, a load lock system, or another type of component that provides environmental isolation. For example, in various implementations, the insertion point **113** may provide a vacuum-pressure environment or a low pressure gas seal between a controlled environment within the cooling system **114** and a room temperature environment. In various implementations, the vacuum-pressure environment may be milli-Torr pressure. In various

implementations, the cooling system **114** maintains a cryogenic thermal environment for the resonator **110** and the sample holder **102**. In some cases, the cooling system **114** can maintain a cryogenic temperature of the resonator **110** and the sample holder **102**. In the example shown in FIG. **1**, the cooling system **114** resides in thermal contact with the resonator **110** and the sample holder **102**. In some cases, the cooling system **114** cools to liquid helium temperatures (e.g., approximately 4 Kelvin), liquid nitrogen temperatures (e.g., approximately 77 Kelvin), or at another cryogenic temperature. In some cases, the cooling system **114** includes a dry cryostat. In some cases, the cooling system **114** can be implemented with or without the use of liquid cryogenics, for example, as a continuous flow helium or nitrogen cryostat (e.g., 4-300 Kelvin), as a variable temperature pulsed-tube refrigerator (e.g., 3.5-300 Kelvin), a pumped helium cryostat (e.g., 1-10 Kelvin), a helium-3 refrigerator (e.g., 250-400 milliKelvin), a dilution refrigerator (e.g., 5-100 milliKelvin), or another type of system or combination of systems. In some implementations, the resonator **110** and the sample holder **102** are both held at cryogenic temperatures. In some cases, the resonator **110** and the sample holder **102** are immersed in a cryogenic liquid or a cryogenic gas, and may be held in a vacuum-pressure environment during operation. In some cases, the sample holder **102**, the resonator **110**, or both are held at a higher temperature (e.g., room temperature, etc.).

[0040] In the example shown in FIG. **1**, a primary magnet system **116** generates a primary magnetic field that the resonator **110** and the sample holder **102** are exposed to during operation. In various implementations, the primary magnet system **116** may be located within the cooling system **114** or outside of the cooling system **114**. The primary magnet system **116** generates a magnetic field in the controlled environment of the resonator **110** and the sample holder **102**. The example primary magnet system **116** shown in FIG. **1** can be implemented as a superconducting solenoid, an electromagnet, a permanent magnet or another type of magnet that generates the primary magnetic field. In various implementations, the magnetic field is homogeneous over the volume of a sample region defined by the resonator **110**. In some instances, a gradient system generates one or more gradient fields that spatially vary over the sample volume. In some cases, the gradient system includes multiple independent gradient coils that can generate gradient fields that vary along different spatial dimensions of the sample region.

[0041] In the example shown in FIG. **1**, a spin ensemble in the sample region of the resonator **110** interacts with the resonator **110**. The primary magnetic field generated by the primary magnet system **116** quantizes the spin states and sets the Larmor frequency of the spin ensemble. Control of the spin magnetization can be achieved, for example, by a radio-frequency or microwave magnetic field generated by the resonator **110**. In the example shown in FIG. **1**, the spin ensemble can be any collection of particles having non-zero spin that interact magnetically with the applied fields of the magnetic resonance system **100**. For example, the spin ensemble can include nuclear spins, electron spins, or a combination of nuclear and electron spins. Examples of nuclear spins include hydrogen nuclei (¹H), carbon-13 nuclei (¹³C), and others. In some implementations, the spin ensemble is a collection of identical spin-1/2 free electron spins attached to an ensemble of large molecules.

[0042] In the example shown in FIG. **1**, the resonator **110** is electrically coupled to a spectrometer system **118**. In various implementations, the spectrometer system **118** acquires magnetic resonance data based on magnetic resonance signals generated by an interaction between the resonator **110** and magnetic resonance samples contained in the sample holder **102**. Typically, the resonator **110** has one or more resonance frequencies and possibly other resonance frequencies or modes. The drive frequency can be tuned to the spins' resonance frequency, which is determined by the strength of the primary magnetic field and the gyromagnetic ratio of the spins.

[0043] The example spectrometer system **118** can control the resonator **110** and possibly other components or subsystems in the magnetic resonance system **100** shown in FIG. **1**. The spectrometer system **118** is electromagnetically coupled to (e.g., by coaxial cables, etc.), and

adapted to communicate with, the resonator **110**. For example, the spectrometer system **118** can be adapted to provide a voltage or current signal that drives the resonator **110**; the spectrometer system **118** can also acquire a voltage or current signal from the resonator **110**.

[0044] In some cases, the spectrometer system **118** includes or is connected with a controller, a waveform generator, an amplifier, a transmitter/receiver switch, a receiver, a signal processor, and possibly other components. A spectrometer system **118** can include additional or different features (e.g., a gradient waveform generator, and gradient electronics, etc.). In the example shown in FIG. **1**, the spectrometer system **118** is adapted to communicate with, and may operate based on inputs provided by, one or more external sources, for example, a computer system or another source.

[0045] In some cases, the spectrometer system **118** may operate in multiple modes of operation. In one mode of operation, the spectrometer system **118** generates control signals (e.g., radio frequency signals, microwave signals, etc.) that are delivered to the resonator **110** to control the spin system in the sample. In another mode of operation, the spectrometer system **118** acquires magnetic resonance signals from the resonator **110**. The magnetic resonance signals can be processed (e.g., digitized) and provided to a computer system for analysis, display, storage, or another action. The computer system may include one or more digital electronic controllers, microprocessors or other types of data-processing apparatus. The computer system may include memory, processors, and may operate as a general-purpose computer, or the computer system may operate as an application-specific device.

[0046] FIG. **2** is a perspective view of an example probe **202** that, in various implementations, may be used in the magnetic resonance system **100** or another type of system. The probe **202** includes a linear support element **204** that extends from an anchor plate **203** located on an external surface or access point of a cooling system (e.g., the cooling system **114** in FIG. **1**) to a support plate **205**. In various implementations, the probe **202** may include a plurality of linear support **204** elements such as, for example, two elements, three elements, or more. Thermal baffles **208** are coupled to the linear support element **204** and provide thermal insulation between the cryogenic thermal environment provided by the cooling system and an external ambient environment. In various implementations, the probe **202** may include a plurality of thermal baffles **208** such as, for example, two thermal baffles **208**, three thermal baffles **208**, or more.

[0047] In the example shown in FIG. **2**, a sample transfer arm **201** extends through the anchor plate **203** and through the thermal baffles **208** in a manner generally parallel to the linear support element **204**. The sample transfer arm **201** is disposed within a guide tube **207**. In various implementations, the sample transfer arm **201** is an elongated rod or another type of structure constructed of a material with a low thermal conductivity and low coefficient of thermal expansion. In various implementations, the sample transfer arm **201** may be formed of, for example, a high-pressure fiberglass impregnated with epoxy resin such as, for example, G-10 fiberglass laminate. A sample holder (e.g., the sample holder **102** shown in FIG. **1**) is coupled to the first end of the sample transfer arm **201**. A resonator package **206** containing a resonator (e.g., the resonator **110** shown in FIG. **1**) is coupled to the support plate **205** opposite the linear support element **204**.

[0048] FIG. **3** is a perspective view of the example resonator package **206** in a probeless magnetic resonance system. In various implementations, the resonator package **206** is coupled to a mounting structure **302**. The mounting structure **302** is disposed within a cooling system (e.g., the cooling system **114** shown in FIG. **1**) and provides a fixed location of the resonator package **206**. In various implementations, the mounting structure **302** is constructed of a material having a high thermal conductivity and provides cooling of the resonator package **206** through galvanic contact. Additionally, the mounting structure **302** may be used to position the resonator package in three-dimensional space relative to the primary magnetic field. The sample mount should feature an empty space at its center, allowing ample room for the sample holder to be removed through the bottom slot of the resonator package. In various implementations, such positioning may be accomplished using for example linear actuators, rotary actuators, or a combination of linear

actuators and rotary actuators. The sample transfer arm **201** extends through the guide tube **207** from the resonator package **206** to outside the cryogenic thermal environment. For purposes of illustration, FIG. **3** the resonator package **206** is illustrated without the cover so that a position of an example sample holder **306** is visible. Thus, in the arrangement shown in FIG. **3**, the linear support structure **204** and the thermal baffle **208** are omitted.

[0049] FIG. **4** is a perspective view of the example resonator package **206**. In the view shown in FIG. **4**, a cover of the resonator package **206** has been removed so that an example resonator chip **420** and the sample holder **306** are visible. The example resonator package **206** includes a housing **402** and a package insert **404**. A resonator floor **406** is cantilevered from the package insert **404**. In various implementations, the resonator floor **406** is constructed of an electrically conductive material such as, for example, copper or other electrically conductive material. This choice ensures a solid electrical ground for the resonator. The resonator chip **420** is coupled to a face of the resonator floor **406**. The resonator chip **420** includes a dielectric substrate **408**, a ground plane (not shown) on a first side of the substrate **408** contacting the resonator floor **404**, and conductors **410** on a second, opposite side of the substrate **408**. In various implementations, a resonator may include additional or different features, and the components of a resonator may be arranged as shown in FIG. **4** or in another manner.

[0050] In the example shown in FIG. **4**, the dielectric substrate **408** may be constructed of dielectric material such as, for example, sapphire, silicon, MgO , LaAlO_3 , or another type of non-magnetic dielectric crystalline material. In some implementations, the conducting material on the dielectric substrate (e.g., the ground plane, the conductors **410**, etc.) can be made of non-superconducting material (e.g., gold, copper, or other conducting material), superconducting material (e.g., niobium, niobium titanium, niobium nitride, aluminum, yttrium barium copper oxide (aka, "YBCO"), magnesium diboride) or a combination of them. Also, enhancements to the resonator's behavior can be achieved through the implementation of various techniques. Such techniques include utilizing composite layers, multilayer films composed of distinct superconducting materials along with normal conducting materials, or incorporating arrays of holes, slots, dielectric, or metallic centers. In various implementations, the conducting materials may be deposited on the substrate **408** by deposition processes or other types of fabrication processes. In various implementations, the substrate **408** may be etched or otherwise conditioned based on standard fabrication processes.

[0051] In some implementations, the ground plane and the conductors **410** may be implemented as thin films on opposite sides of the dielectric substrate **408**. In the example shown in FIG. **4**, the ground plane and the conductors **410** define a microstrip transmission line structure. Generally, a microstrip transmission line structure can include any conducting material (non-superconducting material or superconducting material) on a first surface of a dielectric substrate separated from a ground plane on the opposite surface of the dielectric substrate.

[0052] In the example shown in FIG. **4**, the example sample holder **306** is coupled to the sample transfer arm **201**. During operation, the sample transfer arm **201** translates the sample holder **306** into the housing **402** such that one of the sample containers formed on the sample holder **306** is positioned in a sample region **502** (shown in FIG. **5**) that is defined by the resonator **420**. A toe clamp **414** is attached to the resonator floor **406** and includes a slot **416** formed therein. During operation, the sample holder **306** is received through the slot **416**. Thus, during operation, the toe clamp **414** overhangs a surface of the resonator chip **420** and facilitates proper alignment in two dimensions of the sample holder **306** relative to the resonator chip **420**. In some cases, to ensure controlled elevation of the sample container in relation to the resonator, mechanical elements such as pedestals or tensioners (metallic or dielectric) may be employed.

[0053] FIG. **5** is a plan view of the example resonator package **206** with the housing **402** removed to show structural features. As shown, the resonator floor **406** extends upwardly from the package insert **404**. The resonator chip **420** is coupled to the resonator floor **406**. The conductors **410** are

formed on a surface of the resonator chip **420**. In the example illustrated in FIG. 5, the conductors **410** form a planar conductive path; however, in other implementations, the conductors **410** may be any shape and, in some cases, may be non-planar. For example, in various implementations, the conductors **410** may form a coiled or birdcage type resonator.

[0054] In the example shown in FIG. 5, a microstripline resonator of the resonator chip **420** defines a sample region of the resonator chip **420**. The sample region of the resonator chip **420** is illustrated schematically in FIG. 5 by line **502**. In various implementations, a sample may be positioned in the sample region **502** to increase or maximize a filling factor. A magnetic field generated by the resonator **420** may be described by a vector of B1 field strengths at arbitrary points in three-dimensional space $\vec{B}_1 = B_1(x)\hat{x} + B_1(y)\hat{y} + B_1(z)\hat{z}$ according to the following equation.

$$[00001] \vec{B}_1(\vec{r}) = B_1(x)\hat{x} + B_1(y)\hat{y} + B_1(z)\hat{z}$$

[0055] The filling factor is a dimensionless parameter that describes how much of the total magnetic energy of the resonator field is contained in the sample and may be computed according to the following equation.

$$[00002] h = \frac{\int_{\text{sample}} |\vec{B}_1(\vec{r})|^2 dV}{\int_{\text{space}} |\vec{B}_1(\vec{r})|^2 dV}$$

Where $\vec{B}_1(\vec{r}) = B_1(x)\hat{x} + B_1(y)\hat{y} + B_1(z)\hat{z}$. In general, the filling factor may be computed by simulation of the spatial field profile of the resonator **420**, which is expressed as $\vec{B}_1(\vec{r})$.

[0056] In the example shown in FIG. 5, the sample holder **306** is coupled to the sample transfer arm **201**. Actuation of the sample transfer arm **201** facilitates movement of the sample holder **306** relative to the sample region **502** defined by the microstripline resonator such that a select sample container **504** may be aligned with the sample region **502** of the resonator **420**. The toe clamp **414** facilitates accurate alignment of the sample holder **306** with the resonator chip **420**.

[0057] During operation, each one of the sample containers **504** formed in the sample holder **306** contains a sample for magnetic resonance analysis. Movement of the sample holder **306** via actuation of the sample transfer arm **201** allows one sample container **504** at a time to be positioned in the sample region **502** of the resonator. A calibration sample container **104A** may contain a calibration sample. When the calibration sample is positioned in the sample region **502**, the positioning of the sample holder **306** relative to the resonator may be calibrated. When calibration is complete, the sample holder **306** is moved such that another sample container **504**, containing a sample for analysis, is positioned in the sample region **502** of the resonator. Upon completion of magnetic resonance analysis of one sample, the sample holder **306** is moved again to position a different sample container **504** for analysis of a different sample. Thus, the sample holder **306** facilitates calibration and testing of multiple samples at cryogenic temperatures without the need to remove the samples from the cryogenic thermal environment. Such an arrangement increases throughput of magnetic resonance analysis.

[0058] FIGS. 6A-6B are perspective views of the resonator **420** illustrating positioning of a sample holder relative thereto. FIG. 6A illustrates the sample holder **306** in a first position where the sample container **504** (shown in FIG. 5) containing the calibration sample is positioned in the sample region **502** (shown in FIG. 5). Additionally, FIG. 6A illustrates that the sample holder **306** may, in various implementations, be an elongated prismatic body with a plurality of planar exterior surfaces. In such an implementation, the sample containers **504** can be implemented as channels formed in one of the planar exterior surfaces. FIG. 6B illustrates another example sample holder **602** in a second position where a sample container **604** may be aligned with the sample region **502** of the resonator **420**. FIG. 6B also illustrates that, in some implementations, the sample holder **602** may be, for example, an elongated cylindrical body that defines a lateral surface and that the

sample containers **604** are channels defined in the lateral surface.

[0059] FIG. 7 is a cross-sectional view of the example package insert **404** illustrating the resonator **420** and the sample holder **306**. As shown in FIG. 7, the resonator floor **406** is cantilevered from the package insert **404**. The resonator chip **420** is disposed on a surface of the resonator floor **406**. The sample holder **306** is received through the toe clamp **414** and positioned adjacent to the resonator chip **420** by the sample transfer arm **201**. The sample transfer arm **201** passes the sample holder **306** through a positioning guide **702** that is disposed in a surface of the housing **402** (shown in FIG. 4) opposite the package insert **404**. The positioning guide **702** may be cylindrical in shape and includes a notch **704** formed in a bottom edge. When assembled, the notch **704** engages a cantilevered edge of the resonator floor **406**. Such an arrangement stabilizes the free edge of the resonator floor **406**. During assembly of the resonator package **206** (shown in FIG. 4), the package insert **404** is assembled to the housing **402** via, for example, screws that are received through apertures **706**. During assembly, the positioning guide **702** is removed from the housing **402** in an effort to prevent damage to the resonator floor **406** or the resonator chip **420**. After the package insert **404** is assembled to the housing **402**, the positioning guide **702** is inserted thereby securing the free edge of the resonator floor **406**.

[0060] In the example shown in FIG. 7, interaction of the notch **704** with the resonator floor **406** and interaction of the sample transfer arm **201** with the positioning guide **702** ensures proper spacing between the sample holder **306** and the resonator chip **420**. In various implementations, the toe clamp **414** may include an actuatable compression element (not explicitly shown) that presses the sample holder **306** towards the resonator chip **420** during magnetic resonance data acquisition. In various implementations, the compression element may be, for example, a wedge element that is received into the slot **416** formed in the toe clamp **414** and presses the sample holder **306** into engagement with the resonator chip **420**. In various implementations, the compression element may be mechanically actuated, electrically actuated, or a combination of the two. In other implementations, the compression element may be, for example, hydraulically actuated, pneumatically actuated, or piezoelectric.

[0061] FIG. 8 is a detail view of the positioning guide **702**, the resonator floor **406**, the sample holder **306**, and the resonator **420**. The notch **704** formed in the positioning guide **702** secures the free end of the resonator floor **406**. This facilitates positioning of the resonator floor **406** and helps ensure that, when the sample holder **306** is received into the positioning guide **702**, the sample holder is properly spaced from the resonator **420**. The toe clamp **414** also ensures proper positioning of the sample holder **306** relative to the resonator **420**. As shown in FIG. 8, in various implementations, a cover slip **802** is used in conjunction with the sample holder **306**. The cover slip **802**, is placed over the sample holder **306** and seals the sample containers **504** thereby preventing escape of the samples contained therein. A plurality of ports **804** may be formed in the cover slip **802**. The ports **804** provide fluid communication to the sample containers **504** and allow loading of liquid samples in the sample containers **504** without removal of the cover slip **802**. In various implementations, the ports **804** may be plugged or sealed, for example, with adhesive, wax, or another material with no magnetic resonance signal after a sample has been loaded into the sample container **504**. Sealing of the ports **804** prevents loss of the sample via, for example, evaporation or other mechanisms.

[0062] FIG. 9A is a side view of the sample holder **306**. FIG. 9B is a perspective view of the sample holder **306**. FIG. 9C is a plan view of the sample holder **306**. FIG. 9D is an end view of the sample holder **306**. In the example shown in FIGS. 9A-9D, the sample holder **306** is a prismatic body having a plurality of planar surfaces, and the sample containers **504** are formed in one of the planar surfaces. In various embodiments, the sample containers **504** may incorporate 3D contouring to improve spectral fidelity. One of the sample containers **504A** contains a calibration sample that is used in calibrating the positioning of the sample holder **306** relative to the resonator **420**. In various implementations, the sample holder **306** may be bar-coded, or otherwise marked, to verify

authenticity and identify the specific calibration sample that is contained in the sample container **504A**. The sample containers **504** are spaced from each other a known distance. In various implementations, the sample containers **504** may be spaced a uniform distance from each other, or they may be spaced apart in another arrangement. The sample containers **504** are spaced from each other such that adjacent samples do not interfere electromagnetically with the sample under measurement. Such known spacing between the sample containers **504** allows the sample container **504A**, which contains the calibration sample, to be positioned in the sample region **502** (shown in FIG. 5) for calibration of the position of the sample holder **306** relative to the resonator **420**.

[0063] During calibration, the position of the sample holder **306** may be adjusted via actuation of the sample transfer arm **201** by the actuator (e.g., the actuator **112** shown in FIG. 1) such that the optimum signal is obtained from the calibration sample contained in the sample container **504A**. For instance, the sample holder **306** may be adjusted to determine a position where magnetic resonance data from the calibration sample meets one or more calibration criteria or optimization metrics. In various implementations, this position is used as a reference datum to move to the other sample containers **504** in the sample holder **306**. After completion of calibration, the sample holder **306** may be moved to position another sample container **504** in the sample region **502** in order to conduct magnetic resonance analysis of a first sample. In various implementations, the calibration sample contained in the sample container **504A** may also allow monitoring of performance of the magnetic resonance system, for example, by comparing results with those from factory tests of the same calibration sample. After completing the magnetic resonance analysis of the first sample, the sample holder **306** may again be moved to position a different sample container **504** in the sample region **502** in order to complete magnetic resonance analysis of a second sample. After completing magnetic resonance analysis of the second sample, the sample holder **306** may again be moved relative to the resonator **420** in order to conduct magnetic resonance analysis on a third sample. This process may be performed iteratively until all samples contained in the sample holder **306** have been analyzed.

[0064] In the example shown in FIGS. 9A-9D, the cover slip **802** may, in some implementations, be used in conjunction with the sample holder **306**. In such implementations, the cover slip **802** is placed over the sample holder **306** so as to cover the sample containers **504**. In some implementations, the cover slip **802** may be bonded to the sample holder **306** via, for example, a chemical adhesive. In other implementations, the cover slip **504** and the sample holder **306** may remain separable.

[0065] FIG. 10A is a perspective view illustrating one possible attachment method of the prismatic sample holder **102** to a transfer arm **201**. An aperture **1002A** is formed in an upper aspect of the sample holder **102** and a corresponding aperture is formed in the sample transfer arm **201** at the attachment point. A notch **1003A** is formed in a bottom surface of the sample transfer arm **201**. The notch **1003A** receives a proximal end of the sample holder **102**. When the sample holder **102** is received into the notch **1003A**, a threaded member such as, for example, a set screw **1004** can be utilized to secure the sample holder **102** to the sample transfer arm **201**. The principles discussed relative to FIG. 10A may be applied to any implementation of a sample holder described in this disclosure such as, for example, the sample holder **102**, **306**, **602**, **1202**, **1402**, **1450**, **1501**, or another sample holder.

[0066] FIG. 10B is a perspective view illustrating attachment of the tubular sample holder **602** to a transfer arm **201**. An aperture **1002B** is formed in an upper aspect of the sample holder **602** and a corresponding aperture is formed in the sample transfer arm **201** at the attachment point. A notch **1003B** is formed in a bottom surface of the sample transfer arm **201**. The notch **1003B** receives a proximal end of the sample holder **602**. When the sample holder **602** is received into the notch **1003A**, a threaded member such as, for example, a set screw **1004** can be utilized to secure the sample holder **602** to the sample transfer arm **201**. As illustrated in FIGS. 10A-B and FIGS. 6A-B, the sample holder may incorporate utilize different shapes and forms and is not limited to the form

and shape described herein.

[0067] FIG. **11A** is a flow diagram illustrating a process **1100** for changing samples in a magnetic resonance system using a calibration sample. In various implementations, the magnetic resonance system may be the example magnetic resonance system **100** discussed above with respect to FIG. **1**, or another type of magnetic resonance system. The example process **1100** may include additional or different operations, and the operations may be performed in the order shown or in another order. In some cases, one or more operations may be repeated, omitted, or performed in another manner.

[0068] At **1110**, a sample holder is received into the resonator package. The sample holder can be, for example, the example sample holder **102** shown in FIG. **1**, any of the example sample holders described above and shown in FIGS. **2-9** or FIGS. **13-15**, or another type of sample holder. The resonator package operates in a primary magnetic field of a primary magnet system. The resonator package may be disposed in a cryogenic thermal environment controlled by a cooling system. Translation of the sample holder is facilitated by a sample transfer device (e.g., the sample transfer arm **201** shown in FIG. **2**, or another type of sample transfer device). In various implementations, the sample transfer device may be used in conjunction with a probe (e.g., as illustrated in FIG. **2**); however, in other implementations, the probe may be omitted (e.g., as shown in FIG. **3**). A positioning guide may facilitate positioning of the sample holder relative to the resonator.

[0069] A sample holder of various shapes or forms could be utilized. The sample holder has a plurality of sample containers formed therein. In some implementations, the sample containers may be, for example, a plurality of channels formed in a face of the sample holder. The sample containers may be separated from each other by a uniform distance or otherwise spaced apart. In some implementations, the sample containers are separated by a known, but non-uniform, distance. In some implementations, a cover slip may be used in conjunction with the sample holder. In some implementations, a plurality of ports are formed in the cover slip so as to provide access to the sample containers.

[0070] At **1120**, the sample holder is translated such that a sample container that contains a calibration sample is positioned in the sample region of the resonator. In some implementations, translating the sample holder includes moving the sample holder along a single axis. In other implementations, translating the sample holder includes moving the sample holder along multiple axes including, for example, linearly along two axes or rotationally about one or more axes. Translation of the sample holder is facilitated by an actuator, which may be a mechanical actuator, and electro-mechanical actuator, or any of the actuator types described above with respect to FIG. **1**.

[0071] At **1130**, the position of the sample holder relative to the resonator is calibrated. In some implementations, calibrating the position of the sample holder determines a fiducial reference position of the sample holder. The fiducial reference position can be the position where the magnetic resonance signal obtained from the calibration sample meets a calibration criterion or optimization metric. For example, fiducial reference position can be the position where the observed signal to noise ratio is highest (or above a threshold value), the position where the observed signal strength is highest (or above a threshold value), where the observed linewidth is smallest, or a combination of these or other criteria can be used to select the fiducial reference position. The process of calibrating the position of the sample holder typically includes acquiring magnetic resonance signals from the calibration sample at multiple test positions in the sample region of the resonator, and analyzing the magnetic resonance signals to identify one of the test positions as the ideal position of the calibration sample.

[0072] At **1140**, the sample holder is translated to position a selected sample container, which contains a selected sample for magnetic resonance analysis, in the sample region of the resonator. The fiducial reference position is used as a reference datum when the selected sample container is translated to the sample region. In this manner, the known spacing between the sample containers

combined with knowledge of the fiducial reference position can ensure that the first sample is translated to a correct position relative to the resonator, for example, an ideal position for magnetic resonance analysis.

[0073] At **1150**, magnetic resonance data is acquired from the selected sample. The magnetic resonance data is generated by an interaction between the resonator and the selected sample in the sample region. In various implementations, after magnetic resonance analysis of a first sample in a first sample container, the sample holder may again be translated to position a second sample container, containing a second sample, in the sample region of the resonator. The fiducial reference position can be used again as a reference datum when the second sample is translated to the sample region. Once the second sample is positioned in the sample region, magnetic resonance data may be acquired from the interaction of the second sample with the resonator. This sequence may, in various implementations, be repeated for a third sample, a fourth sample, or more. Thus, multiple samples may be subjected to magnetic resonance analysis without need to remove the sample holder from the cryogenic thermal environment.

[0074] FIG. **11B** is a flow diagram illustrating a process **1102** for changing samples in a magnetic resonance system using frequency-shift calibration. In various implementations, the magnetic resonance system may be the example magnetic resonance system **100** discussed above with respect to FIG. **1**, or another type of magnetic resonance system. The example process **1102** may include additional or different operations, and the operations may be performed in the order shown or in another order. In some cases, one or more operations may be repeated, omitted, or performed in another manner.

[0075] At **1112**, a sample holder is received into the resonator package. The sample holder can be, for example, the example sample holder **102** shown in FIG. **1**, any of the example sample holders described above and shown in FIGS. **2-9** or FIGS. **13-15**, or another type of sample holder. The resonator package operates in a primary magnetic field of a primary magnet system. The resonator package may be disposed in a cryogenic thermal environment controlled by a cooling system. Translation of the sample holder is facilitated by a sample transfer device (e.g., the sample transfer arm **201** shown in FIG. **2**, or another type of sample transfer device). In various implementations, the sample transfer device may be used in conjunction with a probe (e.g., as illustrated in FIG. **2**); however, in other implementations, the probe may be omitted (e.g., as shown in FIG. **3**). A positioning guide may facilitate positioning of the sample holder relative to the resonator.

[0076] A sample holder of various shapes or forms could be utilized. The sample holder has a plurality of sample containers formed therein. In some implementations, the sample containers may be, for example, a plurality of channels formed in a face of the sample holder. The sample containers may be separated from each other by a uniform distance or otherwise spaced apart. In some implementations, the sample containers are separated by a known, but non-uniform, distance. In some implementations, a cover slip may be used in conjunction with the sample holder. In some implementations, a plurality of ports are formed in the cover slip so as to provide access to the sample containers.

[0077] At **1122**, the sample holder is translated such that the leading edge of the sample holder begins to interact with an electric field generated by the resonator. In various implementations, translation of the sample holder may be as described in **1120** of FIG. **11A** or by another method. Interaction of the sample holder with the electric field of the resonator causes the resonant frequency of the resonator to shift. The sample holder possesses a dielectric constant higher than that of vacuum, leading to alterations in the effective dielectric constant of the resonator, resulting in effective values denoted as $\epsilon_{\text{sub.eff}}$. Consequently, the resonant frequency of the resonator may be expressed according to the equation

$$[00003] f_r = \frac{c}{2l\sqrt{\epsilon_{\text{eff}}}}$$

where 'l' signifies the length of the planar $\lambda/2$ -resonator and 'c' denotes the speed of light. The

factor $c/2l$ remains constant. Therefore, if the new $\epsilon_{\text{sub.eff}}$ is greater than the effective dielectric constant of the resonator without the sample holder, the resonant frequency decreases. This phenomenon is illustrated in FIG. 11D, which is a plot 1162 that illustrates the resonant frequency shift induced by sample holders of differing dielectric constants. Furthermore, when the dielectric constant of the sample inside the container differs from that of the material composing the sample container, the resonant frequencies experience shifts based on the distance between the sample and the resonator. Such a shift is illustrated by way of example in FIGS. 11C and 11D, which are plots 1160 of sample-holder position versus resonant frequency shift. As shown in FIG. 11C, at a distance of approximately -4 mm to approximately -2 mm, there is approximately zero shift in resonant frequency. At a position of approximately 2 mm relative to the resonator, the resonant frequency shifts by approximately 30 MHz. At a position of approximately 4 mm, the resonant frequency shifts by approximately 50 MHz. The shape of the resonant frequency shift vs sample holder position curve is repeatable. Thus, the position of the sample holder with respect to the resonator can be determined by monitoring the resonance frequency of the resonator, which may be faster to accomplish compared to monitoring a spin signal. For example, as shown in FIG. 11C, a resonant frequency shift of approximate 20-30 MHz corresponds to the edge of the sample holder being aligned with the middle of the resonator. Such a position is then used as a fiducial reference position, facilitating translation of the sample holder to align each of the sample containers with the resonator with high precision. In addition to monitoring the frequency shift profile of the resonator to determine the sample's position, it is possible to measure and track the profiles of other resonator parameters, such as Q-factor and Insertion Loss. These measurements can be taken as the position of the sample holder is adjusted in relation to the resonator.

[0078] At 1132, the position of the sample holder relative to the resonator is calibrated. In some implementations, calibrating the position of the sample holder determines the fiducial reference position of the sample holder. The fiducial reference position can be the position where the resonant frequency shift of the resonator indicates alignment of the leading edge of the sample holder with the center of the resonator. As noted above, the process of calibrating the position of the sample holder may include measuring a shift of resonant frequency of the resonator to determine an accurate position of the sample holder.

[0079] At 1142, the sample holder is translated to position a selected sample container, which contains a selected sample for magnetic resonance analysis, in the sample region of the resonator. The fiducial reference position is used as a reference datum when the selected sample container is translated to the sample region. In this manner, the known spacing between the sample containers combined with knowledge of the fiducial reference position can ensure that the first sample is translated to a correct position relative to the resonator, for example, an ideal position for magnetic resonance analysis.

[0080] At 1152, magnetic resonance data is acquired from the selected sample. The magnetic resonance data is generated by an interaction between the resonator and the selected sample in the sample region. In various implementations, after magnetic resonance analysis of a first sample in a first sample container, the sample holder may again be translated to position a second sample container, containing a second sample, in the sample region of the resonator. The fiducial reference position can be used again as a reference datum when the second sample is translated to the sample region. Once the second sample is positioned in the sample region, magnetic resonance data may be acquired from the interaction of the second sample with the resonator. This sequence may, in various implementations, be repeated for a third sample, a fourth sample, or more. Thus, multiple samples may be subjected to magnetic resonance analysis without need to remove the sample holder from the cryogenic thermal environment.

[0081] FIG. 12A is a front view of an example sample holder 1202 illustrating sample containers 1204. FIG. 12B is a detailed front view of a sample container 1204. FIG. 13A is a side view of an example sample holder 1202 illustrating sample containers 1204. FIG. 13B is a detailed side view

of a sample container **1204**. The sample container **1204** includes a sample cavity **1206** that is fluidly coupled to a first port **1208** via a first channel **1210**. The sample cavity **1206** is also fluidly coupled to a second port **1212** via a second channel **1214**. The first port **1208** and the second port **1212** are offset from the sample cavity **1206** and disposed on opposite sides of the sample cavity **1206**. During operation, the first port **1208** may be used as a fill port through which a magnetic resonance sample is added to the sample cavity **1206**. In this arrangement, the second port **1212** acts as an air escape port facilitating filling of the sample cavity **1206**. In other implementations, the second port **1212** may be used as a filling port and the first port **1208** may function as an air escape port. Thus, the first port **1208** and the second port **1212** are functionally interchangeable. [0082] In the example shown in FIGS. **12A**, **12B**, **13A**, **13B**, the fill ports are sized to receive a pipette tip, so that pipettes (e.g., standard sized pipettes) can be used for filling the sample cavity **1206**. In various implementations, the volume of the sample cavity **1206** is in the range of approximately 1 μL to approximately 15 μL , which are amounts that are capable of being handled by pipettes. In other implementations, the sample cavity **1206** may be less than approximately 1 μL . In still other implementations, the sample cavity **1206** may be greater than 15 μL . Standard disposable pipette tips are available with tip outer diameters (Ods) down to $\sim 500\text{ }\mu\text{m}$. In various implementations, the first port **1208** and the second port **1212** are approximately 600 μm in diameter, so that such standard pipette tips can be inserted into the ports to transfer liquid into the sample cavity. Having a fill port into which the pipette tip can be inserted simplifies the filling process, and may also enable or enhance automated filling processes. In the example shown, the filling ports extend through a first layer **1302** of the sample holder **1202** (typically, $\sim 250\text{ }\mu\text{m}$) as shown in FIG. **13B**.

[0083] Generally, although larger fill ports may simplify the filling process, they may also allow higher rates of sample solution evaporation. Significant evaporation may result in bubbles forming in the sample solution and changes to the concentration of the sample solution, neither of which is desirable. In the example shown in FIGS. **12A**, **12B**, **13A**, **13B**, the first channel **1210** and the second channel **1214** can be utilized to reduce or avoid sample solution evaporation. As shown, the first channel **1210** and the second channel **1214** exhibit small cross-sections (smaller than the cross-sections of the ports **1208**, **1212**) and form flow paths that fluidly couple the first port **1208** and the second port **1212**, respectively, with the sample cavity **1206**. As illustrated in FIGS. **13A-13B**, the first channel **1210** and the second channel **1214** can be implemented as trenches in the two substrates that make up the sample holder **1202**, and can be small such as, for example, 50 $\mu\text{m} \times 50\text{ }\mu\text{m}$ cross section (e.g., $\sim 100 \times$ smaller area compared to the 600 μm diameter fill port). In other implementations, the first channel **1210** and the second channel **1214** may be as small as, for example 10 $\mu\text{m} \times 10\text{ }\mu\text{m}$ cross section (e.g., $\sim 2500 \times$ smaller area). The first channel **1210** and the second channel **1214** extend from the first port **1208** and the second port **1212**, respectively to opposing diagonal corners of the sample cavity **1206**. Such an arrangement can allow gas from the sample cavity **1206** to exhaust during the filling process, and may prevent residual bubbles in the sample cavity **1206** after filling. The small volume of the first channel **1210** and the second channel **1214** may also limit the amount of sample that resides in the outer portions of the resonator's mode volume, where the resonator field is lower, to limit RF inhomogeneity.

[0084] The relatively large, deep, and offset nature of the first port **1208** and the second port **1212** enables the use of sealants in some implementations to reduce or prevent evaporation of the magnetic resonance sample from the sample cavity **1206**. Materials such as, for example, adhesives, epoxies, waxes, or clays may, in various implementations, be dispensed into the first ports **1208** and the second port **1212** after the sample fill is complete. The offset nature of the first port **1208** and the second port **1212** means that the seal material will have a reduced effect on the magnetic resonance signal from the magnetic resonance sample. In other implementations, the first port **1208** and the second port **1212** may be unsealed.

[0085] As illustrated by way of example in FIG. **13B**, the sample holder **1202** may be formed from

a first layer **1302** that is bonded to a second layer **1304**. In various implementations, the bonding of the first layer **1302** to the second layer **1304** may be via, for example, laser welding, chemical adhesives, contact bonding, combinations thereof, or another bonding method. A first plurality of etches **1306** is formed in the first layer **1302** and a second plurality of etches **1308** is formed in the second layer **1304**. In various implementations, the first plurality of etches **1306** and the second plurality of etches **1308** extend partially through the thickness of the first layer **1302** and the second layer **1304**, respectively. In various implementations, the first plurality of etches **1306** and the second plurality of etches **1308** define portions of the sample cavity **1206**, the first port **1208**, and the second port **1212** such that the sample cavity **1206**, the first port **1208**, and the second port **1212** are formed when the first layer **1302** is aligned with, and bonded to, the second layer **1304**. In implementations where the first port **1208** and the second port **1212** are offset from the sample cavity **1206**, the first plurality of etches **1306** and the second plurality of etches **1308** may also define portions of the first channel **1210** and the second channel **1214** such that the first channel **1210** and the second channel **1212** are also formed when the first layer **1302** is aligned with, and bonded to, the second layer **1304**. The principles discussed relative to FIGS. **12A-B** and **13A-B** may be applied to any implementation of a sample holder described in this disclosure such as, for example, the sample holder **102**, **306**, **602**, **1402**, **1450**, **1501**, or another sample holder.

[0086] FIG. **14A** is a front view of an example sample holder **1402** illustrating sample containers **1404** with offset ports and an adhesive channel **1408**. In various implementations, the sample holder **1402** may be constructed similar to the sample holder **1202** shown in FIGS. **13A-13B**. The sample holder **1402** includes sample containers **1404**. The sample containers **1404** include a first port **1410** that is offset from a sample cavity **1406** and fluidly coupled to a sample cavity **1406** via a first channel **1412** and a second port **1414** that is offset from the sample cavity **1406** and fluidly coupled to the sample cavity **1406** via a second channel **1416**.

[0087] In various implementations, a first adhesive port **1418** and a second adhesive port **1420** are formed in the sample holder **1402**. The first adhesive port **1418** and the second adhesive port **1420** are fluidly coupled to an adhesive channel **1408** that is defined in the sample holder **1402**. The adhesive channel **1408** defines a fluid path that surrounds each of the sample containers **1404**. During operation, a chemical adhesive is injected into the first adhesive port **1418**. The chemical adhesive then fills the adhesive channel **1408** as air is expelled through the second adhesive port **1420**. The chemical adhesive facilitates secure bonding of layers of the sample holder **1402** such as, for example, the first layer **1302** and the second layer **1304** illustrated in FIG. **13B**. In various implementations, the chemical adhesive that is injected into the adhesive channel **1408** may be used alone or, in other implementations, the chemical adhesive may be used in combination with other bonding methodologies including, for example, laser welding or contact bonding.

[0088] Vent ports **1424** are fluidly coupled to the sample cavity **1406**. In various implementations, the vent ports **1424** may be formed in opposite corners of the sample cavity **1406** from the first port **1410** and the second port **1412**; however, in other implementations, the vent ports **1424** may be located elsewhere and fluidly coupled to the sample cavity **1406**. How the sample cavity **1406** fills depends on the wetting characteristics of the sample solution on the material of the sample holder **1402**. In some cases, the solution fills the perimeter of the sample cavity **1406** first, and in some cases can block the first port **1410** and the second port **1414** before the sample cavity **1406** is completely filled, leaving a trapped air bubble in the sample cavity **1406**. Addition of the vent ports **1424** to the sample cavity **1406** facilitates escape of air from the sample cavity **1406** and facilitates complete filling of the sample cavity **1406**.

[0089] FIG. **14B** is a front view of an example sample holder **1450** illustrating sample containers **1456** with multiple ports **1458** and an adhesive channel **1460**. In various implementations, the sample holder **1450** is similar in construction and operation to the sample holder **1402**. The sample holder **1450**, however, omits the first port **1410**, the second port **1414**, the first channel **1412**, and the second channel **1416**. By way of example, the sample holder **1450** includes four ports **1458** that

are fluidly coupled to the sample cavities **1406**. During operation, one of the ports **1458** may be utilized for sample loading, while the remaining ports **1458** may be utilized for air escape. The principles discussed relative to FIGS. **14A-B** may be applied to any implementation of a sample holder described in this disclosure such as, for example, the sample holder **102**, **306**, **602**, **1202**, **1501**, or another sample holder.

[0090] FIG. **14C** is a front view of an example sample holder **1470** illustrating laser weld paths **1472**. FIG. **14D** is a front view of the example sample holder **1470** including an adhesive channel **1476**. The principles discussed relative to FIGS. **14C-D** may be applied to any implementation of a sample holder described in this disclosure such as, for example, the sample holder **102**, **306**, **602**, **1202**, **1501**, or another sample holder. Laser welding is a joining process where a focused laser beam is used to generate heat and pressure. Laser welding is a precise process that results in minimal heat distortion and thermal stress on the sample holder **1770**. The laser weld paths **1472** are disposed around a perimeter of the sample containers **1474**. The laser weld paths **1472** indicate a path traversed by a laser welder and a location of laser welding on the sample holder **1470**. As illustrated in FIG. **14D**, laser welding may be used in conjunction with an adhesive channel **1476**. The adhesive channel may be, in various implementations, similar to the adhesive channel **1408** described above. Use of the adhesive channel **1476** in combination with the laser weld path **1472** facilitates secure bonding of the layers of the sample holder **1470**.

[0091] FIG. **15** is an exploded view of an example three-layer sample holder **1501**. The sample holder **1202** may be formed from a first layer **1502** that is bonded to a second layer **1504**, and a third layer **1506**. In various implementations, the bonding of the first layer **1502** to the second layer **1504** and the third layer **1506** may be via, for example, laser welding, chemical adhesives, contact bonding, combinations thereof, or other bonding method. A first plurality of etches **1508** are formed in the first layer **1502** and a second plurality of etches **1510** are formed in the second layer **1504**. The third layer **1506** is unetched. In various implementations, the first plurality of etches **1508** and the second plurality of etches **1510** extend entirely through the thickness of the first layer **1502** and the second layer **1504**, respectively. In various implementations, the first plurality of etches **1508** and the second plurality of etches **1510** define portions of a sample cavity, a first port, and a second port such that the sample cavity, the first port, and the second port are formed when the first layer **1502** is aligned with, and bonded to, the second layer **1504** and the third layer **1506**. In implementations where the first port and the second port are offset from the sample cavity, the first plurality of etches **1508** and the second plurality of etches **1510** may also define portions of a first channel and a second channel such that the first channel and the second channel are also formed when the first layer **1502** is aligned with, and bonded to, the second layer **1504** and the third layer **1506**.

[0092] The three-layer sample holder **1502** does not require etching to a specific depth—the first plurality of etches **1508** and the second plurality of etches **1510** extend entirely through the first layer **1502** and the second layer **1504**, respectively. This means that either a more traditional etch process could be used, or another type of machining, such as laser cutting or waterjet. In such an arrangement, the surface of the first layer **1502**, the second layer **1504**, and the third layer **1506** would not be affected by the etch process, so it would remain in its native condition, which would facilitate some bonding alternatives, such as contact bonding. Contact bonding is a glueless process whereby two surfaces that have a high degree of conformity are held together by intermolecular forces. Contact bonding requires that the surfaces, for example, the first layer **1502**, the second layer **1504**, and the third layer **1506**, be very smooth and flat. The full-thickness etching of the first plurality of etches **1508** and the second plurality of etches **1510** maintains the outer surfaces of first layer **1502** and the second layer **1504** in their native condition thereby facilitating contact bonding between the first layer **1502**, the second layer **1504**, and the third layer **1506**. The principles discussed relative to FIG. **15** may be applied to any implementation of a sample holder described in this disclosure such as, for example, the sample holder **102**, **306**, **602**, **1202**, **1402**, **1450**, or another

sample holder.

[0093] In a general aspect, the systems and techniques described herein allow for changing samples in a magnetic resonance system.

[0094] In a first example, a magnetic resonance apparatus, includes a resonator. A sample holder includes a plurality of sample containers. A sample transfer device is operable to translate the sample holder relative to the resonator to position any one of the sample containers in a sample region of the resonator.

[0095] Implementations of the first example may include one or more of the following features. For example, in some implementations, the sample transfer device translates the sample holder relative to the resonator to maximize a filling factor of any one of the sample containers relative to the other sample containers. In some implementations, the resonator is configured to generate a control field in the sample region. The sample transfer device is operable to selectively position any one of the sample containers in the sample region.

[0096] In some implementations of the first example, at least one sample container of the plurality of sample containers contains a calibration sample.

[0097] In some implementations of the first example, the plurality of sample containers comprises a plurality of channels defined in the sample holder.

[0098] Implementations of the first example may include one or more of the following features. Each sample container may include a sample cavity and a fill port that is offset from and fluidly coupled to the sample cavity by a sample channel. Each sample container may include an air escape port that is offset from the sample cavity on a side opposite the fill port and is fluidly coupled to the sample cavity by an air escape channel. The fill port may be sized to receive a pipette tip. A sealant may be applied to the fill port and the air escape port. Each of the plurality of channels comprises a surface that is contoured to match a spatial distribution of a resonator control field produced by the resonator. The sample holder may include a cover slip that encloses the plurality of channels. The cover slip defines ports that provide fluid communication to the plurality of channels. The ports may be sealed.

[0099] In some implementations of the first example, the sample transfer arm is operable to transfer the sample holder linearly in a first direction, and the sample containers are spaced apart from each other in the first direction.

[0100] In some implementations of the first example, the sample holder may include an elongated prismatic body defining a plurality of planar exterior surfaces. The sample containers comprise channels defined in one of the plurality of planar exterior surfaces.

[0101] In some implementations of the first example, the sample holder may include an elongated cylindrical body defining a lateral surface. The sample containers may include channels defined in the lateral surface.

[0102] In some implementations of the first example, the plurality of sample containers may include a plurality of capillary tubes in the sample holder.

[0103] Some implementations of the first example include a resonator package that includes the resonator. The sample holder is at least partially disposed within the resonator package. The resonator package may include a positioning guide that facilitates alignment of the sample holder with the resonator.

[0104] In some implementations of the first example, the sample transfer arm comprises a first end that is exposed to room temperature and a second end that is exposed to cryogenic temperature during operation.

[0105] In some implementations of the first example, the second end of the sample transfer arm contacts the sample holder. The first end of the sample transfer arm is mechanically coupled to an actuator that moves the sample transfer arm.

[0106] In some implementations of the first example, the resonator may be a planar resonator. Additional implementations may include a resonator chip. The resonator may be a microstrip

resonator defined on a surface of the resonator chip.

[0107] In some implementations of the first example, the resonator may be a three-dimensional cavity.

[0108] In some implementations of the first example, the resonator may be configured to operate in a primary magnetic field of a probeless magnetic resonance system.

[0109] In some implementations of the first example, the resonator may be configured to operate on a probe in a primary magnetic field of a magnetic resonance system.

[0110] In some implementations of the first example, translation of the sample holder relative to the resonator comprises translation of the sample holder along multiple axes.

[0111] In a second example, a magnetic resonance system includes a primary magnet system that is configured to generate a primary magnetic field. A resonator is configured to interact with a sample in a sample region. A sample holder includes a plurality of sample containers. A sample transfer device that translates the sample holder relative to the resonator to position any one of the sample containers in the sample region.

[0112] Implementations of the second example may include one or more of the following features. The sample transfer device may include a sample transfer rod. Some implementations may include a probe, which includes the resonator. Some implementations may include a cryogenic system that controls a cryogenic thermal environment of the resonator. The sample transfer rod may extend from outside the cryogenic thermal environment to inside the cryogenic thermal environment. The plurality of sample containers may reside in the cryogenic thermal environment. The sample transfer device may be operable to translate the sample holder relative to the resonator to maximize a filling factor of any one of the sample containers relative to the other sample containers. At least one sample container of the plurality of sample containers may contain a calibration sample.

[0113] In some implementations of the second example, the plurality of sample containers may include a plurality of channels defined in the sample holder. Each sample container may include a sample cavity and a fill port that is offset from and fluidly coupled to the sample cavity by a sample channel.

[0114] In some implementations of the second example, each sample container may include an air escape port that is offset from the sample cavity on a side opposite the fill port and is fluidly coupled to the sample cavity by an air escape channel. The fill port may be sized to receive a pipette tip. A sealant may be applied to the fill port and the air escape port.

[0115] In some implementations of the second example each of the plurality of sample containers may include a surface that is contoured to match a spatial distribution of a resonator control field produced by the resonator.

[0116] In some implementations of the second example, the sample transfer device may be operable to transfer the sample holder linearly in a first direction. The sample containers may be spaced apart from each other in the first direction.

[0117] In some implementations of the second example, the sample transfer device may include a first end that is exposed to room temperature and a second end that is exposed to cryogenic temperature during operation. The sample transfer device may be configured to translate the sample holder along multiple axes.

[0118] In a third example, a magnetic resonance sample changer system includes a sample holder including a plurality of sample containers. At least one of the sample containers includes a calibration sample. The sample holder is configured to move relative to a resonator in a primary magnetic field of a magnetic resonance system. The sample holder is configured to mechanically couple with an actuator that positions the sample holder relative to a reference position determined by magnetic resonance measurement of the calibration sample.

[0119] Implementations of the third example may include the actuator. Additional implementations may include a sample transfer arm that mechanically couples the sample holder to the actuator. The actuator may include at least one of a servo, caliper, or micrometer.

[0120] Implementations of the third example may include a position control system that controls the actuator.

[0121] Implementations of the third example may include one or more of the following features. The plurality of sample containers may include a plurality of channels defined in the sample holder. Each sample container may include a sample cavity and a fill port that is offset from and fluidly coupled to the sample cavity by a sample channel. Each sample container may include an air escape port that is offset from the sample cavity on a side opposite the fill port and is fluidly coupled to the sample cavity by an air escape channel. The fill port may be sized to receive a pipette tip. A sealant may be applied to the fill port and the air escape port.

[0122] In some implementations of the third example, each of the plurality of sample containers may include a surface that is contoured to match a spatial distribution of a resonator control field produced by the resonator.

[0123] In some implementations of the third example, the sample holder may include a cover slip that encloses the plurality of channels.

[0124] In some implementations of the third example, the cover slip defines ports that provide fluid communication to the plurality of channels.

[0125] In some implementations of the third example, the port may include plugs.

[0126] In some implementations of the third example, the sample containers are spaced apart from each other in a first direction.

[0127] In some implementations of the third example, the sample holder may include an elongated prismatic body defining a plurality of planar exterior surfaces. The sample containers may include channels defined in one of the plurality of planar exterior surfaces.

[0128] In some implementations of the third example, the sample holder may include an elongated cylindrical body defining a lateral surface. The sample containers may include channels defined in the lateral surface.

[0129] In some implementations of the third example, the plurality of sample containers may include a plurality of capillary tubes in the sample holder.

[0130] In a fourth example, a magnetic resonance method includes receiving a sample holder into a resonator package. The resonator package is disposed in a primary magnetic field of a magnetic resonance system. The resonator package may include a resonator configured to interact with a sample in a sample region. The sample holder may include a first sample and a calibration sample. The sample holder is translated to position the calibration sample in the sample region. The position of the sample holder is calibrated relative to the resonator based on first magnetic resonance signals generated by an interaction between the resonator and the calibration sample. After calibrating the position of the sample holder, the sample holder is translated to position the first sample in the sample region. Magnetic resonance data is acquired based on second magnetic resonance signals generated by an interaction between the resonator and the first sample.

[0131] In some implementations of the fourth example, the sample holder may include a plurality of additional samples. The method may include iteratively translating the sample holder to position one of the plurality of additional samples in the sample region, and acquiring magnetic resonance data based on magnetic resonance signals generated by an interaction between the resonator and the sample currently positioned in the sample region.

[0132] Some implementations of the fourth example may include cooling the sample holder to a cryogenic temperature before calibrating the position of the sample holder.

[0133] In some implementations of the fourth example, translating the sample holder may include linearly translating the sample holder.

[0134] In some implementations of the fourth example, translating the sample holder may include translating the sample holder along multiple axes.

[0135] In some implementations of the fourth example, the magnetic resonance system is the magnetic resonance system of any one of second example.

[0136] In a fifth example, a magnetic resonance system includes a primary magnet system that is configured to generate a primary magnetic field. A resonator is configured to interact with a sample in a sample region. A sample holder includes a plurality of sample containers. A sample transfer device translates the sample holder relative to the resonator to position any one of the sample containers in the sample region.

[0137] Implementations of the fifth example may include one or more of the following features. For example, the sample transfer device may include a sample transfer rod. Further, implementations of the fifth example may include a cryogenic system that controls a cryogenic thermal environment of the resonator. The sample transfer rod extends from outside the cryogenic thermal environment to inside the cryogenic thermal environment. In such implementations, the plurality of sample containers may reside in the cryogenic thermal environment.

[0138] In some implementations of the fifth example, the sample transfer device is operable to translate the sample holder relative to the resonator to maximize a filling factor of any one of the sample containers relative to the other sample containers.

[0139] In some implementations of the fifth example, at least one sample container of the plurality of sample containers contains a calibration sample.

[0140] In some implementations of the fifth example, introduction of the sample holder to an electric field of the resonator induces a shift in a resonant frequency of the resonator. The shift in the resonant frequency indicates a position of the sample holder relative to the resonator.

[0141] Implementations of the fifth example may include one or more of the following features. For example, each sample container may include a sample cavity and a fill port that is fluidly coupled to the sample cavity as well as an air escape port that is fluidly coupled to the sample cavity. Further, in implementations of the fifth example the sample holder may include a first layer having a first plurality of etches formed in a planar surface thereof and a second layer having a second plurality of etches formed in a planar surface thereof. When the first layer is aligned with the second layer, the first plurality of etches and the second plurality of etches align to form the sample cavity, the fill port, and the air escape port.

[0142] Implementations of the fifth example may include one or more of the following features. For example, implementations of the sample holder may include a first layer having a first plurality of etches formed through a full thickness of the first layer, a second layer having a second plurality of etches formed through a full thickness of the second layer, and a third un-etched layer. When the first layer, the second layer, and the third layer are aligned, the first plurality of etches and the second plurality of etches align to form the sample cavity, the fill port, and the air escape port. Further, in implementations of the fifth example, the fill port may be offset from the sample cavity and fluidly coupled to the sample cavity by a sample channel. The air escape port may be offset from the sample cavity on a side opposite the fill port and is fluidly coupled to the sample cavity by an air escape channel.

[0143] In implementations of the fifth example, the sample holder may include an adhesive port formed in one of the first layer or the second layer, an adhesive vent formed in one of the first layer or the second layer, and an adhesive channel that fluidly couples the adhesive port to the adhesive vent and defines a fluid path surrounding each of the sample cavities.

[0144] In implementations of the fifth example, the sample holder may include an elongated prismatic body defining a plurality of planar exterior surfaces, and the sample containers comprise channels defined in one of the plurality of planar exterior surfaces. In other implementations of the fifth example, the sample holder may include an elongated cylindrical body defining a lateral surface, and the sample containers comprise channels defined in the lateral surface. In other implementations of the fifth example, the plurality of sample containers may include a plurality of capillary tubes in the sample holder.

[0145] Implementations of the fifth example may include a resonator package that includes the resonator. The sample holder is at least partially disposed within the resonator package. The

resonator package may include a positioning guide that facilitates alignment of the sample holder with the resonator.

[0146] Implementations of the fifth example may include a resonator chip. In various implementations, the resonator is a planar microstrip resonator defined on a surface of the resonator chip.

[0147] In a sixth example, a magnetic resonance method includes receiving a sample holder into a resonator package. The resonator package is disposed in a primary magnetic field of a magnetic resonance system. The resonator package includes a resonator configured to interact with a sample in a sample region. A position of the sample holder relative to the resonator is calibrated. Based on the calibration, the sample holder is translated to position the sample in the sample region. Magnetic resonance data is acquired based on magnetic resonance signals generated by an interaction between the resonator and the first sample.

[0148] Implementations of the sixth example may include translating the sample holder to position a calibration sample contained in the sample holder in the sample region, and calibrating the position of the sample holder relative to the resonator based on magnetic resonance signals generated by an interaction between the resonator and the calibration sample.

[0149] In implementations of the sixth example, the sample holder may include a plurality of additional samples, and the method may include iteratively translating the sample holder to position one of the plurality of additional samples in the sample region, and acquiring magnetic resonance data based on magnetic resonance signals generated by an interaction between the resonator and the sample currently positioned in the sample region.

[0150] In implementations of the sixth example, calibrating the position of the sample holder may include detecting a shift in a resonant frequency of the resonator, the shift in the resonant frequency resulting from the sample holder entering an electric field of the resonator, and based on the detected shift in the resonant frequency, determining a position of the sample holder relative to the resonator.

[0151] Implementations of the sixth example may include cooling the sample holder to a cryogenic temperature before calibrating the position of the sample holder.

[0152] In a seventh example, a magnetic resonance apparatus, includes a resonator. A sample holder includes a plurality of sample containers. A sample transfer device is operable to translate the sample holder relative to the resonator to position any one of the sample containers in a sample region of the resonator.

[0153] Implementations of the seventh example may include one or more of the following features. For example, the sample transfer device may include a sample transfer rod. Further, implementations of the first example may include a cryogenic system that controls a cryogenic thermal environment of the resonator. The sample transfer rod extends from outside the cryogenic thermal environment to inside the cryogenic thermal environment. In such implementations, the plurality of sample containers may reside in the cryogenic thermal environment.

[0154] In some implementations of the seventh example, the sample transfer device is operable to translate the sample holder relative to the resonator to maximize a filling factor of any one of the sample containers relative to the other sample containers.

[0155] In some implementations of the seventh example, at least one sample container of the plurality of sample containers contains a calibration sample.

[0156] In some implementations of the seventh example, introduction of the sample holder to an electric field of the resonator induces a shift in a resonant frequency of the resonator. The shift in the resonant frequency indicates a position of the sample holder relative to the resonator.

[0157] Implementations of the seventh example may include one or more of the following features. For example, each sample container may include a sample cavity and a fill port that is fluidly coupled to the sample cavity as well as an air escape port that is fluidly coupled to the sample cavity. Further, in implementations of the seventh example the sample holder may include a first

layer having a first plurality of etches formed in a planar surface thereof and a second layer having a second plurality of etches formed in a planar surface thereof. When the first layer is aligned with the second layer, the first plurality of etches and the second plurality of etches align to form the sample cavity, the fill port, and the air escape port.

[0158] Implementations of the seventh example may include one or more of the following features. For example, implementations of the sample holder may include a first layer having a first plurality of etches formed through a full thickness of the first layer, a second layer having a second plurality of etches formed through a full thickness of the second layer, and a third un-etched layer. When the first layer, the second layer, and the third layer are aligned, the first plurality of etches and the second plurality of etches align to form the sample cavity, the fill port, and the air escape port. Further, in implementations of the seventh example, the fill port may be offset from the sample cavity and fluidly coupled to the sample cavity by a sample channel. The air escape port may be offset from the sample cavity on a side opposite the fill port and is fluidly coupled to the sample cavity by an air escape channel.

[0159] In implementations of the seventh example, the sample holder may include an adhesive port formed in one of the first layer or the second layer, an adhesive vent formed in one of the first layer or the second layer, and an adhesive channel that fluidly couples the adhesive port to the adhesive vent and defines a fluid path surrounding each of the sample cavities.

[0160] In implementations of the seventh example, the sample holder may include an elongated prismatic body defining a plurality of planar exterior surfaces, and the sample containers comprise channels defined in one of the plurality of planar exterior surfaces. In other implementations of the seventh example, the sample holder may include an elongated cylindrical body defining a lateral surface, and the sample containers comprise channels defined in the lateral surface. In other implementations of the seventh example, the plurality of sample containers may include a plurality of capillary tubes in the sample holder.

[0161] Implementations of the seventh example may include a resonator package that includes the resonator. The sample holder is at least partially disposed within the resonator package. The resonator package may include a positioning guide that facilitates alignment of the sample holder with the resonator.

[0162] Implementations of the seventh example may include a resonator chip. In various implementations, the resonator is a planar microstrip resonator defined on a surface of the resonator chip.

[0163] While this specification contains many details, these should not be understood as limitations on the scope of what may be claimed, but rather as descriptions of features specific to particular examples. Certain features that are described in this specification or shown in the drawings in the context of separate implementations can also be combined. Conversely, various features that are described or shown in the context of a single implementation can also be implemented in multiple embodiments separately or in any suitable subcombination.

[0164] Similarly, while operations are depicted in the drawings in a particular order, this should not be understood as requiring that such operations be performed in the particular order shown or in sequential order, or that all illustrated operations be performed, to achieve desirable results. In certain circumstances, multitasking and parallel processing may be advantageous. Moreover, the separation of various system components in the implementations described above should not be understood as requiring such separation in all implementations, and it should be understood that the described program components and systems can generally be integrated together in a single product or packaged into multiple products.

[0165] A number of embodiments have been described. Nevertheless, it will be understood that various modifications can be made. For example, in various implementations, a guide system may be utilized to facilitate insertion and placement of the sample holder within the resonator package and to prevent breakage of the sample holder. Such a guide system may include, for example rails

that support opposite edges of the sample holder during placement. Accordingly, other embodiments are within the scope of the following claims.

Claims

1-94. (canceled)

95. An electron spin resonance (ESR) sample holder, comprising: an elongated body comprising a first end and a second end; a plurality of sample containers defined in the elongated body, the plurality of sample containers being spaced apart from each other between the first end and the second end; a plurality of fill ports defined in the elongated body, each fill port of the plurality of fill ports being fluidly coupled to a respective sample container of the plurality of sample containers, each fill port being offset toward the first end of the elongated body relative to the respective sample container; and a plurality of air escape ports defined in the elongated body, each air escape port of the plurality of air escape ports being fluidly coupled to a respective sample container of the plurality of sample containers, each air escape port being offset toward the second end of the elongated body relative to the respective sample container.

96. The ESR sample holder of claim 95, comprising a cover slip that encloses the plurality of sample containers.

97. The ESR sample holder of claim 96, wherein the cover slip comprises a first plurality of ports fluidly coupled to the plurality of fill ports and a second plurality of ports fluidly coupled to the plurality of air escape ports.

98. The ESR sample holder of claim 95, wherein the elongated body comprises: a first layer having a first plurality of etches formed in a planar surface thereof; and a second layer having a second plurality of etches formed in a planar surface thereof, wherein the first plurality of etches and the second plurality of etches align to form the sample containers.

99. The ESR sample holder of claim 95, wherein the elongated body comprises: a first layer having a first plurality of etches formed through a full thickness of the first layer; a second layer having a second plurality of etches formed in the second layer; and a third layer having a third plurality of etches formed in the third layer; and wherein, the first layer, the second layer, and the third layer are aligned such that the first plurality of etches, the second plurality of etches, and the third plurality of etches form the sample containers, the plurality of fill ports and the plurality of air escape ports.

100. The ESR sample holder of claim 95, wherein each sample container of the plurality of sample containers comprises contouring configured to match a spatial distribution of a resonator control field produced by a resonator of an ESR system.

101. The ESR sample holder of claim 100, wherein the contouring is three-dimensional.

102. The ESR sample holder of claim 95, wherein each sample container of the plurality of sample containers comprises a rectangular footprint.

103. The ESR sample holder of claim 95, wherein the elongated body comprises at least one of quartz, sapphire, or borosilicate glass.

104. The ESR sample holder of claim 95, wherein the first end or the second end of the elongated body is configured to mechanically couple with a sample transfer device.

105. The ESR sample holder of claim 95, wherein each of the plurality of fill ports is sized to receive a pipette tip.

106. The ESR sample holder of claim 95, wherein each of the plurality of sample containers has a volume in a range of one to fifteen microliters.

107. The ESR sample holder of claim 95, wherein each of the plurality of sample containers has a volume greater than fifteen microliters.

108. The ESR sample holder of claim 95, comprising: a plurality of first channels defined in the elongated body to provide fluid communication between the plurality of fill ports and the plurality

of sample containers, each first channel of the plurality of first channels defining a respective flow path between a respective fill port and a respective sample container; and a plurality of second channels defined in the elongated body to provide fluid communication between the plurality of air escape ports and the plurality of sample containers, each second channel of the plurality of second channels defining a respective flow path between a respective air escape port and a respective sample container.

109. The ESR sample holder of claim 95, wherein each sample container of the plurality of sample containers is fluidly coupled to four ports defined in the elongated body.

110. A method comprising: receiving an electron spin resonance (ESR) sample holder, comprising: an elongated body comprising a first end and a second end; a plurality of sample containers defined in the elongated body, the plurality of sample containers being spaced apart from each other between the first end and the second end; a plurality of fill ports defined in the elongated body, each fill port of the plurality of fill ports being fluidly coupled to a respective sample container of the plurality of sample containers, each fill port being offset toward the first end of the elongated body relative to the respective sample container; and a plurality of air escape ports defined in the elongated body, each air escape port of the plurality of air escape ports being fluidly coupled to a respective sample container of the plurality of sample containers, each air escape port being offset toward the second end of the elongated body relative to the respective sample container; and adding a plurality of ESR samples into the plurality of sample containers, wherein each ESR sample of the plurality of ESR samples is added into a respective sample container of the plurality of sample containers through the respective fill port that is fluidly coupled to the respective sample container.

111. The method of claim 110, wherein adding an ESR sample into a respective sample container through a respective fill port comprises: inserting a pipette tip into the respective fill port that is fluidly coupled to the sample container; and transferring the ESR sample from a pipette to the respective sample container through the pipette tip and the respective fill port.

112. The method of claim 110, wherein adding an ESR sample into a respective sample container through a respective fill port comprises transferring a liquid sample having a volume in a range of one to fifteen microliters.

113. The method of claim 110, wherein the plurality of air escape ports allow air to escape the plurality of sample containers when the plurality of ESR samples are added.

114. The method of claim 113, comprising sealing the plurality of air escape ports and the plurality of fill ports after adding the plurality of ESR samples.

115. The method of claim 110, comprising mechanically coupling a sample transfer device with the first end or the second end of the elongated body.

116. The method of claim 115, comprising: using the sample transfer device to position a first ESR sample of the plurality of ESR samples in a sample region of a resonator in an ESR system; and acquiring magnetic resonance data based on an interaction between the resonator and the first ESR sample.

117. The method of claim 116, comprising: using the sample transfer device to position a second ESR sample of the plurality of ESR samples in the sample region of the resonator; and acquiring magnetic resonance data based on an interaction between the resonator and the second ESR sample.

118. The method of claim 116, wherein each sample container of the plurality of sample containers comprises contouring that matches a spatial distribution of a resonator control field produced by the resonator.

119. The method of claim 110, wherein each sample container of the plurality of sample containers is fluidly coupled to four ports defined in the elongated body.
