

# US Patent & Trademark Office

## Patent Public Search | Text View

---

United States Patent Application Publication

20250284119

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

SUZUKI; KOICHI

---

### SCANNING APPARATUS, SCANNING METHOD, AND STORAGE MEDIUM

---

#### Abstract

A scanning apparatus according to the present invention includes an observation optical system configured to radiate primary light toward one surface to acquire optical information related to at least a portion of a plurality of spots, a scanning unit configured to perform main scanning in which the observation optical system moves relative to an array plate **101** in a first direction and acquires the optical information and sub-scanning in which the observation optical system moves relative to the array plate **101** in a second direction intersecting the first direction without acquiring the optical information, and an adjustment unit configured to adjust a position of the observation optical system relative to the array plate **101** in an optical axis direction of the primary light. The adjustment unit performs the adjustment in a case where the scanning unit is in a period of the sub-scanning.

---

**Inventors:** SUZUKI; KOICHI (Kanagawa, JP)

**Applicant:** CANON KABUSHIKI KAISHA (Tokyo, JP)

**Family ID:** 91323720

**Appl. No.:** 19/216432

**Filed:** May 22, 2025

#### Foreign Application Priority Data

JP 2022-189179

Nov. 28, 2022

#### Related U.S. Application Data

parent WO continuation PCT/JP2023/041482 20231117 PENDING child US 19216432

---

#### Publication Classification

**Int. Cl.: G02B26/10** (20060101); **G01N21/64** (20060101); **G02B26/08** (20060101)

**U.S. Cl.:**

**CPC G02B26/101** (20130101); **G01N21/6452** (20130101); **G02B26/0816** (20130101);  
**G01N2201/105** (20130101)

---

## **Background/Summary**

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a Continuation of International Patent Application No. PCT/JP2023/041482, filed Nov. 17, 2023, which claims the benefit of Japanese Patent Application No. 2022-189179, filed Nov. 28, 2022, both of which are hereby incorporated by reference herein in their entirety.

### **BACKGROUND OF THE INVENTION**

#### **Field of the Invention**

[0002] The present invention relates to a scanning apparatus, a scanning method, and a storage medium.

#### **Background Art**

[0003] A protein array plate or peptide array plate in which a large number of biomolecules such as proteins and peptides with peptide bonds are immobilized on a substrate is known. By using this, interactions with the large number of biomolecules immobilized on the substrate can be performed simultaneously. Such an array plate is effective for comprehensively analyzing the interactions between bio-derived liquid samples, such as blood, cell extracts, saliva, or interstitial fluid, and a large number of proteins or peptides. Through such analysis, the characteristics of the samples can be measured.

[0004] The immobilized sites of proteins or peptides on the substrate are referred to as spots. As a method for observing a spot that has interacted with a sample, for example, a method for identifying which spot has interacted by labeling the spots with a fluorescent probe is known. A microarray scanner is known as an apparatus for observing an array plate labeled with a fluorescent probe.

[0005] The specification of U.S. Pat. No. 7,911,670 discusses a microarray scanner including an irradiation optical system, a fluorescence detection optical system, and a two-dimensional scanning system. The irradiation optical system has the function of focusing and radiating laser light onto an array plate. The fluorescence detection optical system has the function of detecting the fluorescence light intensity from a spot labeled with a fluorescent probe. The two-dimensional scanning system has the function of acquiring a fluorescence image of a spot on the array plate by performing two-dimensional scanning of the array plate or optical system. Further, a confocal point optical system is used as the fluorescence detection optical system.

[0006] Patent No. 5281756 discusses a scanning optical apparatus that simplifies position adjustment in a height direction during fluorescence image acquisition.

### **CITATION LIST**

#### **Patent Literature**

[0007] PTL 1: U.S. Pat. No. 7,911,670 [0008] PTL 1: Patent No. 5281756

[0009] Due to individual differences in the glass thickness and tilt of an array plate, a confocal optical system with a shallow depth of focus has the issue that acquiring a fluorescence image in focus across the entire surface of the array plate is difficult.

[0010] In the specification of U.S. Pat. No. 7,911,670, automatic focus adjustment using a focus sensor is performed simultaneously with two-dimensional scanning in order to obtain a

fluorescence image in focus across the entire surface of the array plate. However, to perform automatic focus adjustment with high accuracy simultaneously with high-speed two-dimensional scanning of the array plate or optical system, a high-speed feedback control system composed of a high-performance focus sensor and a low-vibration actuator is necessary, which increases the complexity of the apparatus.

[0011] In U.S. Pat. No. 5,281,756, to obtain a fluorescence image in focus across the entire surface of the array plate, two-dimensional scanning needs to be repeated a plurality of times while changing the focusing position and setting parameters, which increases the fluorescence measurement time.

## SUMMARY OF THE INVENTION

[0012] The present invention has been developed in view of the above-described issue and is directed to acquiring in-focus optical information in a short time.

[0013] A scanning apparatus configured to cause an observation optical system to scan over an array plate including a plurality of spots on one surface includes an observation optical system configured to radiate primary light toward the one surface to acquire optical information related to at least a portion of the plurality of spots, a scanning unit configured to perform main scanning in which the observation optical system moves relative to the array plate in a first direction and acquires the optical information and sub-scanning in which the observation optical system moves relative to the array plate in a second direction intersecting the first direction without acquiring the optical information, and an adjustment unit configured to adjust a position of the observation optical system relative to the array plate in an optical axis direction of the primary light, wherein the adjustment unit performs the adjustment in a case where the scanning unit is in a period of the sub-scanning.

[0014] Further features of the present invention will become apparent from the following description of exemplary embodiments with reference to the attached drawings.

---

## Description

### BRIEF DESCRIPTION OF THE DRAWINGS

[0015] FIG. 1 is a schematic diagram illustrating a configuration of a specimen measurement apparatus according to a first embodiment.

[0016] FIG. 2A is an XY-plane view illustrating a configuration of an array plate.

[0017] FIG. 2B is a cross-sectional view illustrating a configuration of the array plate.

[0018] FIG. 3 is a diagram illustrating an internal configuration of a controller according to the first embodiment.

[0019] FIG. 4 is a flowchart illustrating operations of a scanning apparatus according to the first embodiment.

[0020] FIG. 5A is a diagram illustrating a scanning region of the scanning apparatus on the array plate according to the first embodiment.

[0021] FIG. 5B is a diagram illustrating sub-scanning trajectories of the scanning apparatus according to the first embodiment.

[0022] FIG. 5C is a partial enlarged view illustrating sub-scanning trajectories of the scanning apparatus according to the first embodiment.

[0023] FIG. 6A is a diagram illustrating an example of a height distribution of an array substrate in a sub-scanning direction detected by the scanning apparatus according to the first embodiment.

[0024] FIG. 6B is a diagram illustrating an example of a height distribution of an array substrate in a sub-scanning direction detected by the scanning apparatus according to the first embodiment.

[0025] FIG. 7 is a flowchart illustrating operations of acquiring height information according to the first embodiment.

[0026] FIG. **8A** is a diagram illustrating a scanning region on an array plate in an operation of acquiring height information.

[0027] FIG. **8B** is a diagram illustrating a positional relationship of height scanning in an operation of acquiring height information.

[0028] FIG. **8C** is a diagram illustrating a positional relationship of height scanning in an operation of acquiring height information.

[0029] FIG. **9** is a diagram illustrating a positional relationship of sub-scanning of a scanning apparatus according to a second embodiment.

[0030] FIG. **10** is a flowchart illustrating an operation of the scanning apparatus according to the second embodiment.

[0031] FIG. **11** is a diagram illustrating an internal configuration of a controller according to a third embodiment.

[0032] FIG. **12** is a diagram illustrating an operation of a piston-crank mechanism.

[0033] FIG. **13** is a flowchart illustrating an operation of a coordinate calculation circuit according to the third embodiment.

## DESCRIPTION OF THE EMBODIMENTS

[0034] Preferred embodiments of the present invention will be described below with reference to the attached drawings.

### First Embodiment

[0035] FIG. **1** is a schematic diagram illustrating a configuration of a specimen measurement apparatus **100** according to a first embodiment.

[0036] The specimen measurement apparatus **100** functions as a scanning apparatus that scans a target. The specimen measurement apparatus **100** measures a specimen as a target located on one surface of an array plate **101**. A number of biomolecules are immobilized at the spots on a glass slide of the array plate **101** and fluorescently labeled.

[0037] A light source **102** is a semiconductor laser configured to emit light having wavelengths near 670 nm.

[0038] A confocal optical system **103** guides excitation light from the light source **102** to the array plate **101** and guides fluorescence from the spots of the array plate **101** and reflected light from a front surface (upper surface) of the array plate **101** to a light sensor **105**. The confocal optical system **103** is composed of a pinhole, a filter, a dichroic mirror, a quarter-wave plate, a polarizing beam splitter, and a lens. Using the confocal optical system **103** reduces the influence of fluorescent components from the glass slide of the array plate **101** itself, thereby improving the signal-to-noise ratio in the measurement of fluorescent components originating from the spots.

[0039] A light directing unit **104** radiates excitation light onto the spots on the array plate **101**. The light directing unit **104** is composed of a prism for directing the excitation light toward the array plate **101** and a lens for focusing the excitation light onto the spots on the array plate **101**. In the present embodiment, the light directing unit **104** is positioned below the array plate **101** and radiates excitation light upward. Further, the light directing unit **104** is configured to radiate excitation light as primary light onto a target and capture fluorescence as secondary light. The light directing unit **104** corresponds to an example of an observation optical system.

[0040] A light sensor **105** converts light into an electric signal. The light sensor **105** can use a photomultiplier tube and/or a photodiode. The light sensor **105** can separately acquire fluorescence from the spots on the array plate **101** and reflected light from the front surface of the array plate **101**. The light sensor **105** corresponds to an example of a detection unit configured to acquire optical information.

[0041] A piston-crank mechanism **106** moves the light directing unit **104** along a plane perpendicular to an optical axis of the lens of the light directing unit **104** or an optical axis of the excitation light. Specifically, the piston-crank mechanism **106** causes the light directing unit **104** to reciprocate along a short side direction of the array plate **101**. As the light directing unit **104**

reciprocates, excitation light from the light source **102** is scanned in the short side direction of the array plate **101**. It should be noted that the short side direction of the array plate **101** is referred to as a main scanning direction, and reciprocal scanning by the piston-crank mechanism **106** is referred to as main scanning. In other words, the main scanning direction is a direction parallel to the short side of the array plate **101**. In the present embodiment, the stroke of the main scanning is approximately 30 mm. It should be noted that an operation direction of the light directing unit **104** is constrained to the main scanning direction by a guide (not illustrated).

[0042] A pulse motor **107** causes the piston-crank mechanism **106** to rotate at high speed. In the present embodiment, the rotation speed of the pulse motor **107** is approximately 1200 rpm. The pulse motor **107** corresponds to an example of a driving unit.

[0043] An encoder **108** measures the position of the light directing unit **104** in the main scanning direction. The encoder **108** is installed on the piston-crank mechanism **106** and outputs a phase-difference pulse voltage consisting of phases A, B, and Z based on the position of the light directing unit **104** in the main scanning direction. The encoder **108** corresponds to an example of a measurement unit.

[0044] A linear stage **109** moves the array plate **101** along the plane perpendicular to the optical axis of the lens of the light directing unit **104** or the optical axis of the excitation light. Specifically, the linear stage **109** moves the array plate **101** in a direction perpendicular to the main scanning in a horizontal plane. The linear stage **109** is composed of a ball screw and an origin sensor. It should be noted that scanning in the direction perpendicular to the main scanning in the horizontal plane is referred to as sub-scanning. In other words, sub-scanning direction is a direction parallel to a long side of the array plate **101**. There is a placement portion on the linear stage **109** for placing the array plate **101**. A user places the array plate **101** on the placement portion in advance.

[0045] A pulse motor **110** is connected to the linear stage **109**. The rotational motion of the pulse motor **110** is converted into linear motion by the ball screw of the linear stage **109**.

[0046] It should be noted that the piston-crank mechanism **106**, the pulse motor **107**, the linear stage **109**, and the pulse motor **110** correspond to an example of a scanning unit.

[0047] A motor driver **111** is a driver circuit for rotating the pulse motor **110**. In the present embodiment, inputting a one-pulse signal to the motor driver **111** rotates the pulse motor **110** by 0.720 and moves the array plate **101** by 2  $\mu\text{m}$  in sub-scanning direction.

[0048] A linear stage **112** moves the array plate **101** in a vertical direction along the optical axis direction of the lens of the light directing unit **104** or the optical axis direction of the excitation light. The linear stage **112** is composed of a ball screw and an origin sensor. It should be noted that scanning in the vertical direction is referred to as height scanning.

[0049] A pulse motor **113** is connected to the linear stage **112**. The rotational motion of the pulse motor **113** is converted into linear motion by the ball screw of the linear stage **112**.

[0050] The linear stage **112** and the pulse motor **113** correspond to an example of an adjustment unit.

[0051] A motor driver **114** is a driver circuit for rotating the pulse motor **113**. In the present embodiment, inputting a one-pulse signal to the motor driver **114** rotates the pulse motor **113** by 0.720 and moves the array plate **101** by 1  $\mu\text{m}$  upward, that is, in the vertical direction.

[0052] A motor driver **115** is a driver circuit for rotating the pulse motor **107**. In the present embodiment, inputting a one-pulse signal to the motor driver **115** rotates the pulse motor **107** by 0.72° and moves the light directing unit **104** along the main scanning direction.

[0053] A controller **116** controls the entire specimen measurement apparatus **100**. The controller **116** is composed of a field programmable gate array (FPGA), a central processing unit (CPU), and a memory and functions as a computer. The controller **116** performs main scanning, sub-scanning, and height scanning of excitation light on the array plate **101** by controlling the light source **102**, the motor driver **111**, the motor driver **114**, and the motor driver **115**. Further, while scanning, the controller **116** acquires fluorescence signal data (two-dimensional image) based on position

information about the light directing unit **104** measured by the encoder **108** and an output signal from the light sensor **105** and stores the acquired fluorescence signal data (two-dimensional image) in an internal memory.

[0054] The controller **116** acquires height information and tilt information about the array plate **101** and generates drive pulse sequences output to the motor drivers **111** and **114** during sub-scanning and height scanning, as described below. Further, the controller **116** controls the timings of sub-scanning and height scanning and the timing of fluorescence signal data acquisition in synchronization with the position information about the light directing unit **104**. By performing the foregoing control, the thickness and tilt of the array plate **101** are corrected in a case where the light directing unit **104** is outside an imaging region on the array plate **101**, making it possible to perform height scanning so that the entire surface of the array plate **101** is in focus.

[0055] A user interface **117** is an interface for receiving an instruction from the user and displaying a result. The user interface **117** is composed of a keyboard, a mouse, and a display.

[0056] The controller **116** can receive an imaging instruction from the user via the user interface **117** and present image data based on fluorescence signal data to the user via the user interface **117**. Further, the user can specify the imaging region, pixel pitch in the main scanning direction, and pixel pitch in the sub-scanning direction via a graphical user interface (GUI) on the user interface **117** during imaging.

[0057] The piston-crank mechanism **106** includes a crank **118** and a connecting rod **119**.

[0058] The crank **118** is connected to a rotary shaft of the pulse motor **107** and the connecting rod **119** through a joint. The crank **118** has a length  $r$ .

[0059] The connecting rod **119** is connected to the crank **118** and the light directing unit **104** through a joint. The connecting rod **119** has a length  $l$ .

[0060] FIG. 2A is a diagram illustrating the array plate **101** viewed from above, and FIG. 2B is a diagram illustrating the array plate **101** viewed from the side.

[0061] The array plate **101** is composed of a glass slide **201** having a rectangular shape with short and long sides and a number of spots **202** arranged on an upper surface. At each spot **202**, a biomolecule containing a peptide bond is immobilized. Here, a single type of biomolecule is immobilized at a single spot **202**.

[0062] In the present embodiment, the diameter of each spot **202** is approximately 100  $\mu\text{m}$ , and the spot spacing is 200  $\mu\text{m}$ . Further, the array plate **101** has a length of 25 mm in the short side direction (short side) and 75 mm in the long side direction (long side). A point **203** at the upper left of the array plate **101** is defined as an origin, the rightward direction in the short side direction is defined as the positive direction of the X-axis, and the downward direction in the long side direction is defined as the positive direction of the Y-axis. Assuming that the X- and Y-coordinates are in units of  $\mu\text{m}$ , the coordinates of the four corners of the array plate **101** are (0, 0), (25000, 0), (0, 75000), and (25000, 75000).

[0063] In the present embodiment, the stroke of the piston-crank mechanism **106** is 30 mm, which is longer by 5 mm than the length of the array plate **101**. In other words, in main scanning, an additional 2.5 mm is scanned on both the left and right sides of the array plate **101**, with the X-coordinate of the scanning range extending from -2500 to 27500.

[0064] The glass slide **201** includes a region where the spots **202** exist and a region where no spots **202** exist, due to limitations in spot generation or considerations for user grip. A region **204** is a region where the spots **202** on the glass slide **201** exist. In the present embodiment, the coordinates of the four corners of the region **204** are (2000, 2000), (23000, 2000), (2000, 65000), and (23000, 65000). The user can specify the range of Y-coordinates for sub-scanning.

[0065] FIG. 3 is a block diagram illustrating an internal configuration of the controller **116** according to the first embodiment.

[0066] A CPU **301** executes software (program) configured to control the entire controller **116**. The CPU **301** is composed of a micro-processor and a cache memory. The CPU **301** corresponds to an

example of a control unit.

[0067] A bus interface **302** is an interface for connecting the CPU **301** to various peripheral circuits.

[0068] A memory **303** stores an imaging condition input by the user, a parameter of the specimen measurement apparatus **100**, and the fluorescence signal data. The memory **303** can use a double data rate **4** synchronous dynamic random access memory (DDR4-SDRAM) and/or a solid state drive (SSD). The memory corresponds to an example of a storage unit.

[0069] A memory control circuit **304** controls the memory **303** based on a command to access the memory **303** via the bus interface **302**.

[0070] A light source control circuit **305** is a control circuit through which the CPU **301** controls the light source **102**. The light source control circuit **305** is composed of an interface conversion circuit and a digital-to-analog (DA) converter. The CPU **301** can control the on/off state and the light intensity of the laser irradiation from the light source **102** via the light source control circuit **305**.

[0071] A data acquisition circuit **306** is a circuit configured to acquire fluorescence signal data based on the output signal from the light sensor **105** and the position of the light directing unit **104** relative to the array plate **101** and continuously store the acquired fluorescence signal data in the memory **303** based on an instruction from the CPU **301**. The data acquisition circuit **306** is composed of a buffer circuit, an analog-to-digital (AD) converter, an AD converter control circuit, and a direct memory access (DMA) controller. The data acquisition circuit **306** corresponds to an example of an image acquisition unit.

[0072] A motor control circuit **307** generates a control signal to the motor driver **115** for the pulse motor **107**, which is a main scanning motor, based on an instruction from the CPU **301**. The motor control circuit **307** generates a drive pulse voltage based on an instruction from the CPU **301** regarding the rotational speed, acceleration, displacement, rotation direction, and rotation start timing of the pulse motor **107**.

[0073] A motor control circuit **308** generates a control signal to the motor driver **111** for the pulse motor **110**, which is a sub-scanning motor, based on an instruction from the CPU **301**. The motor control circuit **308** generates a drive pulse voltage based on an instruction from the CPU **301** regarding the rotational speed, acceleration, displacement, rotation direction, and rotation start timing of the pulse motor **110**.

[0074] A motor control circuit **309** generates a control signal to the motor driver **114** for the pulse motor **113**, which is a height scanning motor, based on an instruction from the CPU **301**. The motor control circuit **309** generates a drive pulse voltage based on an instruction from the CPU **301** regarding the rotational speed, acceleration, displacement, rotation direction, and rotation start timing of the pulse motor **113**.

[0075] A coordinate calculation circuit **310** counts phase-difference pulse signals of the two phases A and B from the encoder **108** and calculates the position of the light directing unit **104**. In the present embodiment, the encoder **108** has a resolution of 1  $\mu\text{m}$ . In a case where either the phase-A signal or the phase-B signal changes in level and the phase-A signal is ahead in phase compared to the phase-B signal, the coordinate calculation circuit **310** increases the coordinates of the light directing unit **104** by 1  $\mu\text{m}$ . Further, in a case where either the phase-A signal or the phase-B signal changes in level and the phase-B signal is ahead in phase compared to the phase-A signal, the coordinate calculation circuit **310** decreases the coordinates of the light directing unit **104** by 1  $\mu\text{m}$ .

[0076] A synchronization circuit **311** generates trigger signals to the data acquisition circuit **306**, the motor control circuit **308**, and the motor control circuit **309** based on coordinate information calculated by the coordinate calculation circuit **310**. Here, the trigger signal to the data acquisition circuit **306** is referred to as a data acquisition trigger signal, the trigger signal to the motor control circuit **308** is referred to as a sub-scanning trigger signal, and the trigger signal to the motor control circuit **309** is referred to as a height scanning trigger signal.

[0077] Upon receiving the data acquisition trigger signal, the data acquisition circuit **306** controls an internal AD converter, acquires a single piece of data output by the light sensor **105**, and stores the acquired output data in the memory **303** via the internal DMA controller.

[0078] Upon receiving the sub-scanning trigger signal, the motor control circuit **308** outputs a drive pulse sequence corresponding to the displacement of the pixel pitch in the sub-scanning direction to the motor driver **111**. The pixel pitch in the sub-scanning direction is specified by the user at the start of imaging and stored in the memory **303**.

[0079] Upon receiving the height scanning trigger signal, the motor control circuit **309** outputs a drive pulse sequence corresponding to the displacement in the height scanning direction to the motor driver **114**. The displacement in the height scanning direction is calculated by the CPU **301**. A calculation method will be described below.

[0080] A communication circuit **312** is a circuit for connecting the specimen measurement apparatus **100** to an external network. A communication method using a communication protocol conforming to the Ethernet standard is employed. Connecting the specimen measurement apparatus **100** to an external personal computer (external PC) or an external server enables remote control of imaging and data storage in external high-capacity storage.

[0081] A user interface (UI) circuit **313** is a circuit for connecting the specimen measurement apparatus **100** to the user interface **117**. The UI circuit **313** is composed of an input circuit from the keyboard and the mouse and an image forming circuit for controlling the display.

[0082] It should be noted that the peripheral circuits that constitute the controller **116** are implemented on a semiconductor chip, such as a FPGA or an ASIC, and operate in synchronization with the clock. In the present embodiment, the clock frequency is 100 MHz.

[0083] FIG. **4** is a flowchart illustrating operations in an imaging process performed by the specimen measurement apparatus **100** according to the first embodiment. The flowchart in FIG. **4** is realized by the CPU **301** of the controller **116** executing the program.

[0084] FIGS. **5A** to **5C** are diagrams illustrating the positional relationship of sub-scanning on the array plate **101** in the imaging process, as well as the array plate **101** as viewed from above.

[0085] FIGS. **6A** and **6B** are diagrams illustrating the positional relationship of height scanning on the array plate **101** in the imaging process, as well as the array plate **101** as viewed from the side (long side). The Z=0 position on the vertical axis represents the horizontal reference plane. FIGS. **6A** and **6B** differ in the thickness and tilt of the placed array plates.

[0086] In **S401**, the CPU **301** reads an imaging condition based on an imaging instruction from the user. The user inputs the imaging condition in advance via the user interface **117**. The CPU **301** stores the acquired imaging condition in the memory **303**. Here, points **501** (X1, Y1) and **502** (X2, Y2) indicating the imaging region on the array plate **101**, a pixel pitch Xp in the main scanning direction, a pixel pitch Yp in the sub-scanning direction, and a rotational speed Xs in the main scanning direction are input as imaging conditions. In the present embodiment, X1=500, X2=22500, Y1=500, Y2=64500, Xp=10 μm, Yp=10 μm, and Xs=1200 rpm. The memory **303** is, in other words, a storage unit configured to store information about the imaging region defined with respect to the surface (one surface) of the array plate **101** that includes the plurality of spots **202**.

[0087] The CPU **301** sets the imaging condition in the synchronization circuit **311**. Here, the rectangular region with the points **501** and **502** as diagonals on the array plate **101** is referred to as an imaging region **503**. Further, the CPU **301** calculates the number of pixels  $N_x = (X_2 - X_1) / X_p$  in the main scanning direction and the number of pixels  $N_y = (Y_2 - Y_1) / Y_p$  in the sub-scanning direction. In the present embodiment,  $N_x = 2200$ , and  $N_y = 6400$ .

[0088] In **S402**, the CPU **301** acquires height information about the array plate **101** and acquires tilt information based on the height information. The CPU **301** corresponds to an example of an acquisition unit. The tilt information corresponds to an example of information about the array plate. The height from the horizontal reference plane to the front surface of the array plate **101**, i.e., the surface with the spots **202**, is referred to as height information. Further, the tilt of the array plate



**101** in the sub-scanning direction relative to the horizontal reference plane is referred to as tilt information. Here, the CPU **301** acquires height information Z3 and Z4 for two Y-coordinates Y3 and Y4 through measurement. In the present embodiment, Y3=750, and Y4=65000.

[0089] In a case where the tilt is as illustrated in FIG. 6A,  $Z4 > Z3$ , whereas in a case where the tilt is as illustrated in FIG. 6B,  $Z3 < Z4$ . A height information acquisition method will be described below with reference to a flowchart illustrated in FIG. 7.

[0090] Tilt information K is calculated using the following (equation 1):

[00001]  $K = (Z4 - Z3) / (Y4 - Y3)$ . (equation1)

[0091] In S403, the CPU **301** calculates a target height of a sub-scanning position (each row) from the reference plane based on the imaging condition, the height information, and the tilt information K. Here, a target height Z(Y) of a sub-scanning position at a coordinate Y is given by the following (equation 2):

[00002]  $Z(Y) = K \times (Y - Y3) + Z3$ . (equation2)

[0092] In FIGS. 6A and 6B, a target height **601** corresponds to the Z-coordinate of the front surface of the array plate **101**.

[0093] In S404, the CPU **301** instructs the motor control circuits **307**, **308**, and **309** to move the array plate **101** and the light directing unit **104** to an imaging start position.

[0094] In the present embodiment, the X-coordinate of the imaging start position is at the end of the scanning range of the piston-crank mechanism **106**, and the X-coordinate value is -2500. The Y-coordinate of the imaging start position is Y1 specified by the imaging condition. Further, a Z-coordinate Z1 of the imaging start position is calculated using Z(Y1) in (equation 1).

[0095] In S405, the CPU **301** starts main scanning to move the light directing unit **104** in the main scanning direction (scanning process). Specifically, the CPU **301** instructs the motor control circuit **307** to rotate the pulse motor **107** at the rotational speed Xs. As the pulse motor **107** is rotated, the light directing unit **104** starts reciprocating in the X-direction. The X-coordinate of the light directing unit **104** is calculated for each clock by the encoder **108** and the coordinate calculation circuit **310** and output to the synchronization circuit **311**.

[0096] In S406, the CPU **301** instructs the light source control circuit **305** to cause the light source **102** to start light emission. As the light source **102** emits light, irradiation of the array plate **101** begins through the light directing unit **104**.

[0097] In S407, the synchronization circuit **311** determines whether the light directing unit **104** has reached a line feed position. In a case where the X-coordinate of the light directing unit **104** output from the coordinate calculation circuit **310** moves from the imaging region to outside the imaging region, the synchronization circuit **311** determines that the light directing unit **104** has reached the line feed position. In a case where the current main scanning direction is a forward direction (direction in which the X-coordinate increases), when the X-coordinate of the light directing unit **104** exceeds X2, the light directing unit **104** is determined to have reached the line feed position. Scanning in the forward direction is represented by a trajectory **504** in FIG. 5B. On the other hand, in a case where the current main scanning direction is a return direction (direction in which the X-coordinate decreases), when the X-coordinate of the light directing unit **104** becomes less than X1, the synchronization circuit **311** determines that the light directing unit **104** has reached the line feed position. Scanning in the return direction is represented by a trajectory **506** in FIG. 5B. The initial value of the main scanning direction is the forward direction, and thereafter, the return direction and the forward direction alternate each time the line feed position is reached.

[0098] In a case where the line feed position has been reached, the synchronization circuit **311** outputs the sub-scanning trigger signal and the height scanning trigger signal to execute S416 in parallel with S417 and S418. In a case where the line feed position has not been reached, the synchronization circuit **311** outputs neither the sub-scanning trigger signal nor the height scanning trigger signal, and the processing proceeds to S408.

[0099] In **S408**, the synchronization circuit **311** determines whether the light directing unit **104** has reached a sampling position. The sampling position refers to the point on the array plate **101** where fluorescence signal data is acquired. It should be noted that while a case where the sampling position is a position different from the spots is described, the sampling position may be the same position as a spot. An X-coordinate  $P(N)$  of the Nth sampling position is expressed by the following (equation 3):

[00003]  $P(N) = X1 + Xp \times (N + 1 / 2) (N = 0, 1, \dots, Nx - 1)$ . (equation3)

[0100] The sampling position refers to a plurality of points on a trajectory, such as a point **508** in FIG. 5B, and the pitches in the X- and Y-directions are respectively  $Xp$  and  $Yp$ . Further, the initial value of the sampling position is  $P(0)$  and stored in the synchronization circuit **311**. In the first sampling position determination, the light directing unit **104** is determined to have reached the sampling position in a case where the X-coordinate of the light directing unit **104** output from the coordinate calculation circuit **310** has passed  $P(0)$  in the forward direction (direction in which the X-coordinate increases). In the second and following sampling position determinations, the light directing unit **104** is determined to have reached the sampling position in a case where the X-coordinate of the light directing unit **104** output from the coordinate calculation circuit **310** has passed the sampling position updated in **S410** described below.

[0101] In a case where the sampling position has been reached, the synchronization circuit **311** outputs the data acquisition trigger signal, and the processing proceeds to **S409**. In a case where the sampling position has not been reached yet, the synchronization circuit **311** does not output the data acquisition trigger signal, and the processing proceeds to **S411**.

[0102] In **S409**, the data acquisition circuit **306** acquires optical information from the sampling position. Specifically, the data acquisition circuit **306** outputs a conversion start signal of the internal AD converter and performs AD conversion of an output voltage from the light sensor **105**. The AD-converted fluorescence signal data is stored in the memory **303** via the internal DMA controller of the data acquisition circuit **306** and the memory control circuit **304**. After  $Nx \times Ny$  pieces of data are stored in the memory **303**, the data acquisition circuit **306** sets an internal data acquisition complete register to "1", whereas in a case where  $Nx \times Ny$  pieces of data are not stored in the memory **303**, the data acquisition circuit **306** sets the internal data acquisition complete register to "0". The process of **S409** is performed while the light directing unit **104** reciprocates in the main scanning direction, but is not performed while the light directing unit **104** reciprocates in the sub-scanning direction.

[0103] In **S410**, the synchronization circuit **311** updates the sampling position internally stored. In a case where the current main scanning direction is the forward direction (direction in which the X-coordinate increases), the synchronization circuit **311** updates the sampling position  $P(N)$  to  $P(N+1)$ , whereas in a case where the current main scanning direction is the return direction (direction in which the X-coordinate decreases), the synchronization circuit **311** updates the sampling position  $P(N)$  to  $P(N-1)$ .

[0104] In **S411**, the CPU **301** determines whether data acquisition has been completed. The CPU **301** reads the data acquisition complete register of the data acquisition circuit **306**, and in a case where the value of the data acquisition complete register is 1, the CPU **301** determines that data acquisition has been completed, and the processing proceeds to **S412**. In a case where the value of the data acquisition complete register is 0, the CPU **301** determines that data acquisition has not been completed, and the processing proceeds to **S407**.

[0105] In **S412**, the CPU **301** instructs the light source control circuit **305** to stop the emission of light from the light source **102**. As the light source **102** stops emitting light, irradiation of the array plate **101** through the light directing unit **104** stops.

[0106] In **S413**, the CPU **301** stops main scanning. Specifically, the CPU **301** instructs the motor control circuit **307** to stop the rotation of the pulse motor **107**. As the rotation of the pulse motor

**107** stops, the reciprocation of the light directing unit **104** in the X-direction stops.

[0107] In **S414**, the CPU **301** instructs the motor control circuits **307**, **308**, and **309** to move the array plate **101** and the light directing unit **104** to a stop position. The X-, Y-, and Z-coordinates of the stop position are 0. The movement to the stop position is performed by returning each axis to the origin using a Z-phase pulse signal of the encoder **108**, an origin sensor signal in the linear stage **109**, and an origin sensor signal of the linear stage **112**.

[0108] In **S415**, the CPU **301** reads the  $N_x \times N_y$  pieces of fluorescence signal data stored in the memory **303**, performs data compression and format conversion processing, and generates a fluorescence image file in Tagged Image File Format (TIFF). The fluorescence image file is stored in the memory **303** and presented to the user via the UI circuit **313** and the user interface **117**. Further, it is transferred to an external data server via the communication circuit **312** based on an instruction from the user.

[0109] In **S416**, the CPU **301** performs sub-scanning to move the array plate **101** in the sub-scanning direction (scanning process). Specifically, the CPU **301** instructs the motor control circuit **308** to move the array plate **101** by  $Y_p$  in the sub-scanning direction. Here, the number of pulses output to the motor driver **111** by the motor control circuit **308** is  $Y_p/M_y$ , where  $M_y$  is the displacement of the array plate **101** when one pulse of a voltage pulse signal is transmitted to the motor driver **111**. In the present embodiment,  $M_y = 2 \text{ } \mu\text{m}$ . Sub-scanning is represented by trajectories **505** and **507** in FIG. 5B, and the movement distance in the Y-direction is  $Y_p$ .

[0110] FIG. 5C is an enlarged view of the trajectories **505** and **507**. The trajectory **505** includes a linear trajectory **511** along the forward direction of the main scanning direction, a semicircular trajectory **512**, and a linear trajectory **513** along the return direction of the main scanning direction. Further, the trajectory **507** includes a linear trajectory **514** along the return direction of the main scanning direction, a semicircular trajectory **515**, and a linear trajectory **513** along the forward direction of the main scanning direction. As described above, the trajectories **505** and **507** in the present embodiment each include trajectories corresponding to at least two movement directions.

[0111] Based on an instruction from the CPU **301**, the motor control circuit **308** outputs a pulse signal to the motor driver **111** at a speed that allows sub-scanning to complete while the light directing unit **104** is outside the imaging region in the main scanning direction.

[0112] In **S417**, the CPU **301** reads the target heights before and after sub-scanning from the memory **303** to perform height scanning. Specifically, the CPU **301** reads  $Z(Y + Y_p)$  and  $Z(Y)$  and calculates the displacement in height scanning. The displacement in height scanning varies depending on the current Y-coordinate, but the number of output pulses and the rotation direction of the pulse motor **113** are calculated so that the height in the Z-direction after movement is closest to the target height  $Z(Y + Y_p)$  at the Y-coordinate after sub-scanning in **S416**.

[0113] A specific calculation direction will be described below.

[0114] Here, the displacement of the array plate **101** when one pulse of a voltage pulse signal is transmitted to the motor driver **114** is denoted as  $M_z$ . In the present embodiment,  $M_z = 1 \text{ } \mu\text{m}$ .

[0115]  $\text{Round}M_z(x)$  denotes the multiple of  $M_z$  closest to a number  $x$ ,  $\text{ABS}(x)$  denotes the absolute value of a number, and  $\text{Sign}(x)$  denotes the sign of a number. The multiple of  $M_z$  closest to the target height is referred to as the target number of pulses. The target number of pulses takes discrete values and corresponds to a height **602** in FIGS. 6A and 6B. The number of pulses output to the motor driver **114** by the motor control circuit **309** is expressed by the following (equation 4):

$$[00004] \quad Z_p = \text{ABS}(\text{Round}M_z(Z(Y + Y_p)) - \text{Round}M_z(Z(Y))). \quad (\text{equation4})$$

[0116]  $\text{Round}M_z(Z(Y))$  takes discrete values close to the front surface of the array plate **101** as specified by the height **602** in FIGS. 6A and 6B.

[0117] Further, a movement direction  $\text{Dir}$  of the array plate in the height direction is expressed by the following (equation 5):

$$[00005] \quad \text{Dir} = \text{Sign}(\text{Round}M_z(Z(Y + Y_p)) - \text{Round}M_z(Z(Y))). \quad (\text{equation5})$$

[0118] The positive direction of Dir is defined as vertically upward, in the direction in which the distance between the light directing unit **104** and the array plate **101** increases. In a case where the tilt of the array plate **101** is as illustrated in FIG. 6A, the value of Dir is 1, whereas in a case where the tilt of the array plate **101** is as illustrated in FIG. 6B, the value of Dir is -1.

[0119] In **S418**, the CPU **301** performs height scanning to adjust the array plate **101** along the vertical direction in order to acquire in-focus optical information (adjustment process). Specifically, the CPU **301** instructs the motor control circuit **309** to move the array plate **101** by  $Z_p$  in the movement direction Dir. In a case where the value of Dir is positive, the array plate **101** is moved upward, whereas in a case where the value of Dir is negative, the array plate **101** is moved downward. The process of **S418** is performed based on scanning sequence information indicating that the light directing unit **104** has reached the line feed position in **S407**. In other words, the CPU **301** determines whether to perform height scanning based on the scanning sequence information.

[0120] The number of pulses output to the motor driver **111** by the motor control circuit **309** is  $Z_p/M_z$ . Based on an instruction from the CPU **301**, the motor control circuit **309** outputs a pulse signal to the motor driver **114** at a speed that allows height scanning to complete while the light directing unit **104** is outside the imaging region in the main scanning direction. Thus, height scanning is performed during the sub-scanning period. In other words, height scanning and sub-scanning are performed in parallel. On the other hand, height scanning is not performed during the main scanning period.

[0121] In a case where sub-scanning in **S416** and height scanning in **S418** are complete, the processing proceeds to **S419**.

[0122] In **S419**, the synchronization circuit **311** updates the current main scanning direction and the Y-coordinate. In other words, in a case where the previous main scanning direction is the forward direction, the synchronization circuit **311** updates the main scanning direction to the return direction and the line feed position to X1. On the other hand, in a case where the previous main scanning direction is the return direction, the synchronization circuit **311** updates the main scanning direction to the forward direction and the line feed position to X2. Further, the synchronization circuit **311** increments the previous Y-coordinate by  $Y_p$  to update the current Y-coordinate, and the processing proceeds to **S411**.

[0123] FIG. 7 is a flowchart illustrating operations in acquiring height information about the array plate **101**, which corresponds to part of the process of **S402** described above. It should be noted that in the process illustrated in the flowchart in FIG. 7, unlike the process illustrated in the flowchart in FIG. 4, reflected light signal data is acquired and analyzed while height scanning is performed at equal pitch intervals without performing sub-scanning, and the height of the front surface of the array plate **101** is calculated.

[0124] FIGS. 8A and 8B are diagrams illustrating positional relationships of height scanning on the array plate **101** in an operation of acquiring height information, as well as the array plate **101** as viewed from the side (short side). FIG. 8C plots, for each height, the intensity of reflected light acquired by the light sensor **105** during height scanning, with the horizontal axis representing the magnitude of the light intensity and the vertical axis representing the acquired height.

[0125] In **S701**, the CPU **301** sets a parameter for height information acquisition in the synchronization circuit **311**. A Y-coordinate  $Y_h$  of a position where height information acquisition is performed, the pixel pitch  $X_p$  in the main scanning direction, the pixel pitch  $Z_p$  in the height scanning direction, points **801** ( $X_5, Z_5$ ) and **802** ( $X_6, Z_6$ ) indicating a height scanning range on the XZ-plane, and the rotational speed  $X_s$  in the main scanning direction are set as the parameters.

[0126] A rectangular region **803** with the points **801** and **802** as its diagonals on the XZ-plane is referred to as a height scanning region. The CPU **301** calculates the number of pixels  $N_x = (X_6 - X_5)/X_p$  in the main scanning direction and the number of pixels  $N_z = (Z_6 - Z_5)/Z_p$  in the height scanning direction in advance. In the present embodiment,  $X_5 = 500$ ,  $X_6 = 22500$ ,  $Z_5 = 2000$ ,  $Z_6 = 6000$ ,  $X_p = 10$  [um],  $Z_p = 10$  [um], and  $X_s = 1200$  [rpm]. In this case,  $N_x = 2200$ , and  $N_z = 400$ .

[0127] In **S702**, the CPU **301** instructs the motor control circuits **307**, **308**, and **309** to move the array plate **101** and the light directing unit **104** to a height information acquisition start position. [0128] In the present embodiment, the X-coordinate of the height information acquisition start position is at the end of the scanning range of the piston-crank mechanism **106**, and the X-coordinate value is  $-2500$ . The Y-coordinate of the height information acquisition start position is  $Y_h$ , as specified by the parameter. Further, the Z-coordinate of the height information acquisition start position is  $Z_5$ , as specified by the parameter.

[0129] In **S703**, the CPU **301** starts main scanning. This process is similar to the process of **S405** described above.

[0130] In **S704**, the CPU **301** causes the light source **102** to start light emission, thereby starting light irradiation. This process is similar to the process of **S406** described above.

[0131] In **S705**, the synchronization circuit **311** determines whether the light directing unit **104** has reached the line feed position. In a case where the X-coordinate of the light directing unit **104** output from the coordinate calculation circuit **310** moves from the imaging region to outside the imaging region, the synchronization circuit **311** determines that the light directing unit **104** has reached the line feed position. In a case where the current main scanning direction is the forward direction (direction in which the X-coordinate increases), when the X-coordinate of the light directing unit **104** exceeds  $X_6$ , the light directing unit **104** is determined to have reached the line feed position. Scanning in the forward direction is represented by a trajectory **804** in FIG. **8B**. On the other hand, in a case where the current main scanning direction is the return direction (direction in which the X-coordinate decreases), when the X-coordinate of the light directing unit **104** becomes less than  $X_5$ , the synchronization circuit **311** determines that the light directing unit **104** has reached the line feed position. Scanning in the return direction is represented by a trajectory **806** in FIG. **8B**. The initial value of the main scanning direction is the forward direction, and thereafter, the return direction and the forward direction alternate each time the line feed position is reached.

[0132] In a case where the line feed position has been reached, the synchronization circuit **311** outputs the height scanning trigger signal, and the processing proceeds to **S714**. In a case where the line feed position has not been reached, the synchronization circuit **311** does not output the height scanning trigger signal, and the processing proceeds to **S706**.

[0133] In **S706**, the synchronization circuit **311** determines whether the light directing unit **104** has reached the sampling position. This process is similar to the process of **S408** described above. The sampling position refers to a plurality of points on a trajectory, such as points **808** in FIG. **8B**, and the pitches in the X- and Z-directions are respectively  $X_p$  and  $Z_p$ . In a case where the sampling position has been reached, the synchronization circuit **311** outputs the data acquisition trigger signal, and the processing proceeds to **S707**. In a case where the sampling position has not been reached yet, the synchronization circuit **311** does not output the data acquisition trigger signal, and the processing proceeds to **S709**.

[0134] In **S707**, the data acquisition circuit **306** acquires reflected light signal data from the sampling position. This process is similar to the process of **S409** described above. After  $N_x \times N_z$  pieces of data are stored in the memory **303**, the data acquisition circuit **306** sets the internal data acquisition complete register to "1", whereas in a case where  $N_x \times N_z$  pieces of data are not stored in the memory **303**, the data acquisition circuit **306** sets the internal data acquisition complete register to "0".

[0135] In **S708**, the synchronization circuit **311** updates the sampling position internally stored. This process is similar to the process of **S410** described above.

[0136] In **S709**, the CPU **301** determines whether data acquisition has been completed. This process is similar to the process of **S411** described above. In a case where the CPU **301** determines that data acquisition has been completed, the processing proceeds to **S710**. In a case where the CPU **301** determines that data acquisition has not been completed, the processing proceeds to **S705**.

[0137] In **S710**, the CPU **301** stops the emission of light from the light source **102**. This process is similar to the process of **S412** described above.

[0138] In **S711**, the CPU **301** stops main scanning. This process is similar to the process of **S413** described above.

[0139] In **S712**, the CPU **301** moves the array plate **101** and the light directing unit **104** to the stop position. This process is similar to the process of **S414** described above.

[0140] In **S713**, the CPU **301** reads  $N_x \times N_z$  pieces of reflected light signal data stored in the memory **303**, analyzes the read data, and calculates height information about the array plate. Specifically,  $N_x$  pieces of data acquired at the same height are summed and then averaged to calculate the average light intensity for each height. When the average light intensities are arranged by Z-coordinate, two peaks corresponding to the front and back surfaces of the array plate **101** are present. In FIG. **8C**, a peak **809** indicates a peak caused by the reflected light from the front surface of the array plate **101**, and a peak **810** indicates a peak caused by the reflected light from the back surface of the array plate **101**. A Z-coordinate **811** indicating the peak **809** with the greater Z-coordinate, i.e., the peak corresponding to the front surface, of the two peaks corresponds to height information at the position  $Y_h$ .

[0141] In **S714**, the CPU **301** instructs the motor control circuit **309** to move the array plate **101** by  $Z_p$  in the height scanning direction. The number of pulses output to the motor driver **114** by the motor control circuit **309** is  $Z_p/M_z$ , where  $M_z$  is the displacement of the array plate **101** when one pulse of a voltage pulse signal is transmitted to the motor driver **114**. Height scanning is represented by trajectories **805** and **807** in FIG. **8B**, and the movement distance in the Z-direction is  $Z_p$ .

[0142] Based on an instruction from the CPU **301**, the motor control circuit **309** outputs a pulse signal to the motor driver **114** at a speed that allows height scanning to complete while the light directing unit **104** is outside the imaging region in the main scanning direction.

[0143] In **S715**, the synchronization circuit **311** updates the current main scanning direction and the Z-coordinate. In other words, in a case where the previous main scanning direction is the forward direction, the synchronization circuit **311** updates the main scanning direction to the return direction and the line feed position to X5. On the other hand, in a case where the previous main scanning direction is the return direction, the synchronization circuit **311** updates the main scanning direction to the forward direction and the line feed position to X6. Further, the synchronization circuit **311** increments the previous Z-coordinate by  $Z_p$  to update the current Z-coordinate, and the processing proceeds to **S709**.

[0144] In acquiring tilt information in **S402** described above, the process in the flowchart in FIG. **7** is performed on each of the Y-coordinates  $Y_3$  and  $Y_4$  to obtain height information  $Z_3$  for the Y-coordinate  $Y_3$  and height information  $Z_4$  for the Y-coordinate  $Y_4$ , and the tilt information  $K$  is calculated using (equation 1). By calculating the tilt information  $K$  as described above, a target height can be calculated for each sub-scanning position in **S403**.

[0145] As described above, the specimen measurement apparatus **100** according to the present embodiment performs height scanning during the sub-scanning period to adjust the array plate **101** along the vertical direction. Thus, in-focus optical information can be acquired in a short time.

[0146] Further, in the present embodiment, the synchronization circuit **311** is used to perform sub-scanning and height scanning in synchronization with the position of the light directing unit **104**. Since sub-scanning and height scanning are performed while the light directing unit **104** is outside the imaging region, it is unnecessary to move the array plate **101** in the imaging region. Therefore, the impact of vibrations caused by driving the array plate **101** can be reduced. Further, since the specimen measurement apparatus **100** does not include a high-speed servo control system composed of a high-performance focus sensor and a low-vibration actuator, a fluorescence image in focus across the entire surface of the array plate **101** can be acquired with a simple configuration.

[0147] Further, in the present embodiment, the pulse motor **107** for main scanning rotates at a

constant speed during imaging to move the light directing unit **104**, and sub-scanning and height scanning are performed while the light directing unit **104** is outside the imaging region. Since it is unnecessary to temporarily stop the pulse motor **107** for main scanning before sub-scanning and height scanning, the reciprocating scanning of the light directing unit **104** can be performed at high speed, which reduces the imaging time.

[0148] Further, in the present embodiment, two-dimensional scanning, involving both main scanning and sub-scanning, is performed while correcting individual differences in thickness and tilt of the entire array plate **101** based on height information and tilt information acquired at least at two points in advance. Thus, compared to three-dimensional scanning of the array plate **101**, a fluorescence image in focus across the entire surface of the array plate **101** can be acquired in a short time.

[0149] Further, in the present embodiment, the target number of pulses closest to the target height is calculated for each sub-scanning position (each row). Therefore, in a case where the amount and direction of height scanning are not predetermined values, especially in a case where the displacement differs for each row, it is possible to adjust to a height close to the target height. Thus, even in a case where it is difficult to predict the height and tilt of the array plate **101** in advance due to individual differences in thickness and tilt of the array plate **101**, and in the method of placing the array plate **101**, a fluorescence image in focus across the entire surface of the array plate can be acquired.

[0150] Further, in the present embodiment, main scanning is also performed during height information acquisition, and Nx pieces of data are averaged, enabling stable peak detection even in a case where there is partial contamination or liquid on the array plate **101**. Thus, the accuracy of the acquired height information can be improved compared to detecting a peak at a single point on the array plate **101** for each height scanning position.

[0151] Further, in the present embodiment, the synchronization circuit **311** is used to sample fluorescence signal data in synchronization with the position of the light directing unit **104**. Compared to a case where data sampling and sub-scanning are performed at a constant interval without synchronizing with the position of the light directing unit **104**, evenly spaced data can be acquired across the entire array plate **101**, thereby improving positional accuracy in acquiring a captured image.

[0152] It should be noted that while the present embodiment describes the case where the imaging region **503** covers the entire region **204** and all spots on the array plate **101** are imaged, this is not a limiting case. For example, the user can set part of the region **204** as the imaging region **503**. In this case, the imaging time can be reduced by scanning of only the part that includes the spot of interest to the user.

[0153] It should be noted that while the present embodiment describes the case where height information is acquired using the peak of the reflected light from the front surface of the glass slide **201**, this is not a limiting case. For example, height information can be acquired using the peak position of the fluorescence signal luminance from some of the spots on the array plate **101**. In this case, although the spots need to be irradiated with light to acquire height information, since the light sensor **105** does not need to acquire reflected light, the number of components in the optical system can be reduced.

[0154] It should be noted that while the present embodiment describes the case with a single wavelength from the light source **102**, a plurality of light sources, a plurality of optical systems, and a plurality of light sensors for each wavelength may be included, and the array plate **101** may be irradiated with excitation light with a plurality of wavelengths. By comparing the fluorescence signals generated by the excitation light with the plurality of wavelengths, the properties of the biomolecule at the spot can be analyzed in more detail.

[0155] It should be noted that while the present embodiment describes the case where the light directing unit **104** is moved in the main scanning direction, this is not a limiting case. For example,

the array plate **101** may be moved in the main scanning direction, or the light directing unit **104** and the array plate **101** may both be moved in the main scanning direction. In other words, at least one of the light directing unit **104** and the array plate **101** may be moved relative to the other in the main scanning direction.

[0156] Further, while the present embodiment describes the case where the array plate **101** is moved in the sub-scanning direction, this is not a limiting case. For example, the light directing unit **104** may be moved in the sub-scanning direction, or the light directing unit **104** and the array plate **101** may both be moved in the sub-scanning direction. In other words, at least one of the light directing unit **104** and the array plate **101** may be moved relative to the other in the sub-scanning direction.

[0157] Further, while the present embodiment describes the case where the array plate **101** is moved in the vertical direction, this is not a limiting case. For example, the light directing unit **104** may be moved in the vertical direction, or the light directing unit **104** and the array plate **101** may both be moved in the vertical direction. In other words, at least one of the light directing unit **104** and the array plate **101** may be moved relative to the other in the vertical direction to adjust the relative position of the light directing unit **104** and the array plate **101**.

## Second Embodiment

[0158] A second embodiment differs from the first embodiment in the scanning method of the light directing unit **104** and the fluorescence signal data sampling method. In the first embodiment, signal acquisition from the light sensor **105** is performed in the forward and return directions of main scanning, and sub-scanning and height scanning are performed during outside the imaging region at both ends of the array plate **101**. In the present embodiment, signal acquisition from the light sensor **105** is performed during main scanning in the forward direction, and sub-scanning and height scanning are performed during main scanning in the return direction.

[0159] It should be noted that the configuration of the specimen measurement apparatus **100** and the internal configurations of the array plate **101** and the controller **116** in the present embodiment are similar to those in FIGS. **1**, **2A**, **2B**, and **3**, so that the description of these will be omitted.

[0160] FIG. **9** is a diagram illustrating a positional relationship of sub-scanning on the array plate **101** in the imaging process. FIG. **10** is a flowchart illustrating an operation in a process of imaging the array plate **101** performed by the specimen measurement apparatus **100** according to the present embodiment.

[0161] **S1001** to **S1006** are similar to **S401** to **S406** in the first embodiment.

[0162] In **S1007**, the synchronization circuit **311** determines whether the light directing unit **104** has reached the line feed position. In a case where the X-coordinate of the light directing unit **104** output from the coordinate calculation circuit **310** moves from the imaging region to outside the imaging region, the synchronization circuit **311** determines that the light directing unit **104** has reached the line feed position. In a case where the current main scanning direction is the forward direction (direction in which the X-coordinate increases), when the X-coordinate of the light directing unit **104** exceeds  $X_2$ , the light directing unit **104** is determined to have reached the line feed position. Scanning in the forward direction is represented by a trajectory **901** in FIG. **9**. On the other hand, in a case where the current main scanning direction is the return direction (direction in which the X-coordinate decreases), when the X-coordinate of the light directing unit **104** becomes less than  $X_1$ , the synchronization circuit **311** determines that the light directing unit **104** has reached the line feed position. Scanning in the return direction is represented by a trajectory **902** in FIG. **9**. The initial value of the main scanning direction is the forward direction, and thereafter, the return direction and the forward direction alternate each time the line feed position is reached.

[0163] In a case where the line feed position has been reached, the processing proceeds to **S1017**. In a case where the line feed position has not been reached, the processing proceeds to **S1008**.

[0164] In **S1008**, the synchronization circuit **311** determines whether the current main scanning direction is the forward direction or the return direction. In a case where it is the forward direction,



the processing proceeds to **S1009**. In a case where it is the return direction, the processing proceeds to **S1012**.

[0165] In **S1009**, the synchronization circuit **311** determines whether the light directing unit **104** has reached the sampling position. The sampling position refers to the point on the array plate **101** where fluorescence signal data is acquired. The X-coordinate  $P(N)$  of the Nth sampling position is expressed by (equation 3) described above. The sampling position refers to a plurality of points on a trajectory, such as points **903** in FIG. 9, and the pitches in the X- and Y-directions are respectively  $X_p$  and  $Y_p$ , with the same coordinates as in the first embodiment. Further, the initial value of the sampling position is  $P(0)$  and stored in the synchronization circuit **311**. In the first sampling position determination, the light directing unit **104** is determined to have reached the sampling position in a case where the X-coordinate of the light directing unit **104** output from the coordinate calculation circuit **310** has passed  $P(0)$  in the forward direction (direction in which the X-coordinate increases). In the second and following sampling position determinations, the light directing unit **104** is determined to have reached the sampling position in a case where the X-coordinate of the light directing unit **104** output from the coordinate calculation circuit **310** has passed in the forward direction the sampling position updated in **S1011** described below.

[0166] In a case where the sampling position has been reached, the synchronization circuit **311** outputs the data acquisition trigger signal, and the processing proceeds to **S1010**. In a case where the sampling position has not been reached yet, the synchronization circuit **311** does not output the data acquisition trigger signal, and the processing proceeds to **S1012**.

[0167] **S1010** is similar to the process of **S409** in the first embodiment.

[0168] In **S1011**, the synchronization circuit **311** updates the sampling position internally stored. Since the current main scanning direction is the forward direction (direction in which the X-coordinate increases), the synchronization circuit **311** updates the sampling position  $P(N)$  to  $P(N+1)$ . However, in a case where  $N=N_x-1$ ,  $P(N)$  is updated to  $P(0)$ .

[0169] **S1012** to **S1016** are similar to **S411** to **S415** in the first embodiment.

[0170] In **S1017**, the synchronization circuit **311** determines whether the current main scanning direction is the forward direction or the return direction. In a case where it is the forward direction, the synchronization circuit **311** outputs the sub-scanning trigger signal and the height scanning trigger signal to execute **S1018** in parallel with **S1019** and **S1020**. In a case where it is the return direction, the processing proceeds to **S1021**.

[0171] In **S1018**, the CPU **301** performs sub-scanning simultaneously with main scanning in the return direction. Specifically, the CPU **301** instructs the motor control circuit **308** to move the array plate **101** by  $Y_p$  in the sub-scanning direction. Here, the number of pulses output to the motor driver **111** by the motor control circuit **308** is  $Y_p/M_y$ , where  $M_y$  is the displacement of the array plate **101** when one pulse of a voltage pulse signal is transmitted to the motor driver **111**. In the present embodiment,  $M_y=2\text{ }\mu\text{m}$ .

[0172] Here, sub-scanning is performed simultaneously with main scanning in the return direction, resulting in a substantially linear inclined trajectory, such as the trajectory **902** in FIG. 9, that intersects both the X- and Y-directions. It should be noted that the movement distance of the component in the Y-direction is  $Y_p$ .

[0173] Based on an instruction from the CPU **301**, the motor control circuit **308** outputs a pulse signal to the motor driver **111** at a speed that allows sub-scanning to complete while the light directing unit **104** is moved in the return direction of the main scanning direction.

[0174] **S1019** is similar to the process of **S417** in the first embodiment.

[0175] In **S1020**, height scanning is performed to acquire in-focus optical information. Specifically, the CPU **301** instructs the motor control circuit **309** to move the array plate **101** by  $Z_p$  in the movement direction  $Dir$ . In a case where the value of  $Dir$  is positive, the array plate **101** is moved upward, whereas in a case where the value of  $Dir$  is negative, the array plate **101** is moved downward.

[0176] The number of pulses output to the motor driver **111** by the motor control circuit **309** is Zp/Mz. Based on an instruction from the CPU **301**, the motor control circuit **309** outputs a pulse signal to the motor driver **114** at a speed that allows height scanning to complete while the light directing unit **104** is moved in the return direction of the main scanning direction. Thus, height scanning is performed while sub-scanning is performed and while main scanning in the return direction is performed. In other words, height scanning is performed in parallel with sub-scanning and main scanning in the return direction. On the other hand, height scanning is not performed while main scanning in the forward direction is performed.

[0177] In a case where sub-scanning in **S1018** and height scanning in **S1020** are complete, the processing proceeds to **S1021**.

[0178] **S1021** is similar to the process of **S419** in the first embodiment.

[0179] As described above, the specimen measurement apparatus **100** according to the present embodiment acquires fluorescence signal data only during main scanning in the forward direction, and sub-scanning and height scanning are performed during main scanning in the return direction without acquiring fluorescence signal data. Thus, although the imaging time is doubled, since the main scanning direction during data acquisition can be aligned, the impact of position and angle errors of the light directing unit **104** in the forward and return paths can be reduced.

[0180] Further, in the present embodiment, since the time spent in main scanning in the return direction can be allocated to sub-scanning and height scanning, the speed of sub-scanning and height scanning can be reduced. Thus, the impact of residual vibrations caused by sub-scanning and height scanning can be reduced, which can improve the quality of the fluorescence image.

[0181] It should be noted that while the present embodiment describes the case where fluorescence signal data is acquired only during main scanning in the forward direction, fluorescence signal data may be acquired only during main scanning in the return direction, and sub-scanning and height scanning may be performed during main scanning in the forward direction without acquiring fluorescence signal data. This can be realized by reversing the forward and return directions in the determinations in **S1008** and **S1017** described above.

[0182] It should be noted that while the present embodiment describes the operation in the imaging process, sampling and height scanning can be performed only in one of the forward and return directions also in the process of acquiring height information. In this case, as in the imaging process, the impact of position and angle errors of the light directing unit **104** can be reduced, and the impact of residual vibrations caused by height scanning can also be reduced, which can improve the accuracy of the acquired height information.

### Third Embodiment

[0183] A third embodiment differs from the first embodiment in that the encoder **108** for measuring the position of the light directing unit **104** in the main scanning direction is not included. In the first embodiment, the coordinate calculation circuit **310** calculates the position of the light directing unit **104** based on a signal from the encoder **108**. In the present embodiment, the position of the light directing unit **104** is calculated based on a motor drive pulse signal from the motor control circuit **307**. It should be noted that the configuration of the specimen measurement apparatus **100** and the array plate **101** in the present embodiment are similar to those in FIGS. **1**, **2A**, and **2B**, so that the description of these will be omitted.

[0184] FIG. **11** is a block diagram illustrating an internal configuration of a controller **1116** in the third embodiment. The configuration of the controller **1116** is similar to that in the first embodiment, except that the coordinate calculation circuit **310** is replaced with a coordinate calculation circuit **1310** and the encoder **108** is not included.

[0185] The coordinate calculation circuit **1310** is a circuit that calculates the position of the light directing unit **104** based on the drive pulse voltage from the motor control circuit **307**.

[0186] FIG. **12** is a diagram illustrating an operation of the piston-crank mechanism.

[0187] A position  $x$  of the light directing unit **104** is expressed by the following (equation 6), where

r is the length of the crank **118** of the piston-crank mechanism, l is the length of the connecting rod **119** of the piston-crank mechanism, and  $\theta$  is the angle of the pulse motor **107**.

[00006][Math1]  $x = r \cos \theta + \sqrt{l^2 - r^2 \sin^2 \theta}$ . (equation6)

[0188] By multiplying the rotation angle per pulse by the number of drive pulses,  $\theta$  can be calculated. Since r and l are known values, the coordinates of the light directing unit **104** are calculated using (equation 6) each time a drive pulse is input. However, since the rotation angle per pulse is 0.72° increments, the resulting value of x will also be discrete. Thus, the coordinate calculation circuit **1310** estimates a coordinate between pulses by interpolating using an angular velocity.

[0189] FIG. **13** is a flowchart illustrating an operation performed by the coordinate calculation circuit.

[0190] In **S1301**, the coordinate calculation circuit **1310** sets the values of an internal pulse counter and a time counter to 0.

[0191] In **S1302**, the coordinate calculation circuit **1310** determines whether a rising edge of the drive pulse signal from the motor control circuit **307** has been input. In a case where it has been input, the processing proceeds to **S1303**. In a case where it has not been input, the processing proceeds to **S1311**.

[0192] In **S1303**, the coordinate calculation circuit **1310** determines whether the motor has completed one rotation. For example, in a case where a rotation angle  $\theta_p$  of the pulse motor **107** per pulse is 0.72°, the motor completes one full rotation with **500** pulses. Thus, in a case where a current value  $C_p$  of the pulse counter is 499, it is determined that one full rotation has been completed, and the processing proceeds to **S1310**. On the other hand, in a case where the current value  $C_p$  of the pulse counter is 498 or less, it is determined that one full rotation has not been completed, and the processing proceeds to **S1304**.

[0193] In **S1304**, the coordinate calculation circuit **1310** increments the pulse counter by 1.

[0194] In **S1305**, the coordinate calculation circuit **1310** calculates an angular velocity w by dividing the value of the time counter by a clock cycle. The angular velocity w is calculated using  $w = \theta_p \times T / C_t$ , where  $C_t$  is the value of the time counter, and T is the clock cycle. However, in a case where the value  $C_t$  of the time counter is 0, the angular velocity w is calculated to be 0.

[0195] In **S1306**, the coordinate calculation circuit **1310** sets the time counter to 0.

[0196] In **S1307**, the coordinate calculation circuit **1310** calculates an angle  $\theta$ . The angle  $\theta$  is calculated using  $\theta = C_p \times \theta_p + w \times C_t \times T$ , where  $C_p$  is the value of the pulse counter.

[0197] In **S1308**, the coordinate calculation circuit **1310** calculates an x-coordinate. Specifically, the x-coordinate is calculated by substituting the calculated angle  $\theta$  into (equation 6).

[0198] In **S1309**, the coordinate calculation circuit **1310** outputs the calculated coordinate to the synchronization circuit **311**.

[0199] In **S1310**, the coordinate calculation circuit **1310** sets the time counter to 0.

[0200] In **S1311**, the coordinate calculation circuit **1310** increments the time counter by 1.

[0201] While the operation of the coordinate calculation circuit **1310** has been described with reference to the flowchart, since the coordinate calculation circuit **1310** is implemented on a digital circuit, the coordinate calculation circuit **1310** actually performs the operations of **S1301** to **S1311** at each clock cycle.

[0202] As described above, the present embodiment allows synchronization of main scanning, sub-scanning, height scanning, and data acquisition without using an encoder by estimating the position of the light directing unit **104** from the drive pulse signal from the motor control circuit **307**. Since the specimen measurement apparatus **100** does not include an encoder, manufacturing costs can be reduced.

[0203] It should be noted that while the present embodiment describes the case where the rotation angle  $\theta_p$  of the pulse motor **107** per pulse is set to 0.72°, this is not a limiting case. For example, by

use of a motor driver with a microstep control function in the motor control circuit **307**,  $\theta_p$  can be divided into tens or hundreds of steps, thereby improving the accuracy of estimating the position of the light directing unit **104**.

[0204] It should be noted that while the present embodiment describes the case where the coordinate calculation circuit **1310** calculates the angular velocity from the time difference between the rising edges of the pulse signal, this is not a limiting case. For example, the coordinate calculation circuit **1310** can be configured to operate while the pulse motor **107** rotates at a constant speed, and the angular velocity can be calculated using the rotational speed  $X_s$  in the main scanning direction specified by the user.

[0205] While the present invention has been described in detail based on its preferred embodiments, the present invention is not limited to the specific embodiments, and various forms that do not deviate from the essence of the invention are also included within the scope of the present invention. For example, a portion of the configuration or process from one embodiment may be combined with another embodiment.

[0206] Further, a single hardware component may perform the various types of control described as being performed by the CPU **301**, the synchronization circuit **311**, or the data acquisition circuit **306** in the embodiments described above. Further, a plurality of hardware components (e.g., a plurality of processors or circuits) may share the processes of the various types of control to control the entire apparatus.

#### Other Embodiments

[0207] The present invention can also be realized by executing the following process. Specifically, a program configured to realize the function of the embodiments described above is supplied to a system or an apparatus via a network or various recording media, and a computer (such as a CPU or a microprocessor unit (MPU)) of the system or the apparatus reads the program codes and executes the read program codes. In this case, the program and the recording medium storing the program constitute the present invention.

[0208] Further, the disclosure of the present embodiment includes the following configurations.

#### Configuration 1

[0209] A scanning apparatus configured to cause an observation optical system to scan over an array plate including a plurality of spots on one surface, the scanning apparatus including an observation optical system configured to radiate primary light toward the one surface to acquire optical information related to at least a portion of the plurality of spots, a scanning unit configured to perform main scanning in which the observation optical system moves relative to the array plate in a first direction and acquires the optical information and sub-scanning in which the observation optical system moves relative to the array plate in a second direction intersecting the first direction without acquiring the optical information, and an adjustment unit configured to adjust a position of the observation optical system relative to the array plate in an optical axis direction of the primary light, wherein the adjustment unit performs the adjustment in a case where the scanning unit is in a period of the sub-scanning.

#### Configuration 2

[0210] The scanning apparatus according to Configuration 1, wherein in a case where the scanning unit is in a period of the main scanning, the adjustment unit does not perform the adjustment.

#### Configuration 3

[0211] The scanning apparatus according to Configuration 1 or 2, further including an image acquisition unit configured to acquire a two-dimensional image based on an output signal from the observation optical system and information about a position of the observation optical system relative to the array plate on a plane on which the observation optical system moves relative to the array plate.

#### Configuration 4

[0212] The scanning apparatus according to any one of Configurations 1 to 3, further including a

control unit configured to determine whether to perform the adjustment based on information about a scanning sequence performed by the scanning unit.

#### Configuration 5

[0213] The scanning apparatus according to any one of Configurations 1 to 4, further including a storage unit configured to store information about an imaging region defined with respect to the one surface.

#### Configuration 6

[0214] The scanning apparatus according to any one of Configurations 1 to 5, wherein the sub-scanning includes movement corresponding to two or more movement directions on a plane on which the observation optical system moves relative to the array plate.

#### Configuration 7

[0215] The scanning apparatus according to Configuration 6, wherein the sub-scanning includes movement in the first direction.

#### Configuration 8

[0216] The scanning apparatus according to any one of Configurations 1 to 7, further including an acquisition unit configured to acquire information about the array plate, wherein the adjustment unit performs the adjustment based on the information about the array plate acquired by the acquisition unit.

#### Configuration 9

[0217] The scanning apparatus according to Configuration 8, wherein the information about the array plate includes tilt information about the array plate as viewed from the first direction.

#### Configuration 10

[0218] The scanning apparatus according to Configuration 9, wherein the tilt information about the array plate is calculated based on height information about the array plate acquired at least at two points.

#### Configuration 11

[0219] The scanning apparatus according to any one of Configurations 1 to 10, wherein the scanning unit moves the observation optical system and the array plate relative to each other based on information about a position of the observation optical system and information about a position of the array plate.

#### Configuration 12

[0220] The scanning apparatus according to any one of Configurations 1 to 11, wherein the adjustment unit performs the adjustment based on information about an imaging region from which the optical information is acquired and information about a position of the observation optical system.

#### Configuration 13

[0221] The scanning apparatus according to Configuration 12, wherein in a case where the position of the observation optical system is outside the imaging region, the adjustment unit performs the adjustment.

#### Configuration 14

[0222] The scanning apparatus according to Configuration 12 or 13, wherein the information about the imaging region is information input in advance by a user.

#### Configuration 15

[0223] The scanning apparatus according to any one of Configurations 11 to 14, further including a measurement unit configured to measure the position of the observation optical system, wherein the information about the position of the observation optical system is information acquired based on the position of the observation optical system measured by the measurement unit.

#### Configuration 16

[0224] The scanning apparatus according to any one of Configurations 11 to 14, further including a driving unit configured to move the observation optical system relative to the array plate, wherein

the information about the position of the observation optical system is information acquired based on a signal for driving the driving unit.

#### Configuration 17

[0225] The scanning apparatus according to any one of Configurations 1 to 16, wherein the second direction is a direction perpendicular to the first direction.

#### Configuration 18

[0226] The scanning apparatus according to any one of Configurations 1 to 16, wherein the second direction is a direction that is not perpendicular to the first direction but is inclined relative to the first direction.

#### Configuration 19

[0227] The scanning apparatus according to any one of Configurations 1 to 16, wherein the array plate has a rectangular shape with a short side and a long side when viewed from the one surface, wherein the first direction is a direction parallel to the short side of the array plate, and wherein the second direction is a direction parallel to the long side of the array plate.

#### Configuration 20

[0228] The scanning apparatus according to any one of Configurations 1 to 16, wherein the array plate has a rectangular shape with a short side and a long side when viewed from the one surface, wherein the first direction is a direction parallel to the short side of the array plate, and wherein the second direction is a direction intersecting both the short side and the long side of the array plate.

#### Configuration 21

[0229] The scanning apparatus according to any one of Configurations 1 to 20, wherein the observation optical system is configured to radiate the primary light toward at least a portion of the plurality of spots and capture secondary light from the at least a portion of the plurality of spots.

#### Method 1

[0230] A scanning method for causing an observation optical system to scan over an array plate including a plurality of spots on one surface, the method including performing main scanning in which the observation optical system configured to radiate primary light toward the one surface to acquire optical information related to at least a portion of the plurality of spots moves relative to the array plate in a first direction and acquires the optical information and sub-scanning in which the observation optical system moves relative to the array plate in a second direction intersecting the first direction without acquiring the optical information, and adjusting a position of the observation optical system relative to the array plate in an optical axis direction of the primary light, wherein the adjusting performs the adjustment in a period of the sub-scanning by the scanning.

#### Method 2

[0231] The scanning method according to Method 1, further including acquiring information about the array plate in advance prior to the scanning, wherein the adjusting performs the adjustment based on the acquired information about the array plate.

#### Program 1

[0232] A program for causing a computer to execute the scanning method according to Method 1.

[0233] The present invention is not limited to the embodiments described above, and various changes and modifications can be made without departing from the spirit and scope of the present invention. Therefore, the following claims are appended to define the scope of the present invention.

#### Other Embodiments

[0234] Embodiment(s) of the present invention can also be realized by a computer of a system or apparatus that reads out and executes computer executable instructions (e.g., one or more programs) recorded on a storage medium (which may also be referred to more fully as a 'non-transitory computer-readable storage medium') to perform the functions of one or more of the above-described embodiment(s) and/or that includes one or more circuits (e.g., application specific

integrated circuit (ASIC)) for performing the functions of one or more of the above-described embodiment(s), and by a method performed by the computer of the system or apparatus by, for example, reading out and executing the computer executable instructions from the storage medium to perform the functions of one or more of the above-described embodiment(s) and/or controlling the one or more circuits to perform the functions of one or more of the above-described embodiment(s). The computer may comprise one or more processors (e.g., central processing unit (CPU), micro processing unit (MPU)) and may include a network of separate computers or separate processors to read out and execute the computer executable instructions. The computer executable instructions may be provided to the computer, for example, from a network or the storage medium. The storage medium may include, for example, one or more of a hard disk, a random-access memory (RAM), a read only memory (ROM), a storage of distributed computing systems, an optical disk (such as a compact disc (CD), digital versatile disc (DVD), or Blu-ray Disc (BD)<sup>TM</sup>), a flash memory device, a memory card, and the like.

[0235] The present invention makes it possible to acquire in-focus optical information in a short time.

[0236] While the present invention has been described with reference to exemplary embodiments, it is to be understood that the invention is not limited to the disclosed exemplary embodiments. The scope of the following claims is to be accorded the broadest interpretation so as to encompass all such modifications and equivalent structures and functions.

## Claims

1. A scanning apparatus configured to cause an observation optical system to scan over an array plate including a plurality of spots on one surface, the scanning apparatus comprising: an observation optical system configured to radiate primary light toward the one surface to acquire optical information related to at least a portion of the plurality of spots; a scanning unit configured to perform main scanning in which the observation optical system moves relative to the array plate in a first direction and acquires the optical information and sub-scanning in which the observation optical system moves relative to the array plate in a second direction intersecting the first direction without acquiring the optical information; and an adjustment unit configured to adjust a position of the observation optical system relative to the array plate in an optical axis direction of the primary light, wherein the adjustment unit performs the adjustment in a case where the scanning unit is in a period of the sub-scanning.
2. The scanning apparatus according to claim 1, wherein in a case where the scanning unit is in a period of the main scanning, the adjustment unit does not perform the adjustment.
3. The scanning apparatus according to claim 1, further comprising an image acquisition unit configured to acquire a two-dimensional image based on an output signal from the observation optical system and information about a position of the observation optical system relative to the array plate on a plane on which the observation optical system moves relative to the array plate.
4. The scanning apparatus according to claim 1, further comprising a control unit configured to determine whether to perform the adjustment based on information about a scanning sequence performed by the scanning unit.
5. The scanning apparatus according to claim 1, further comprising a storage unit configured to store information about an imaging region defined with respect to the one surface.
6. The scanning apparatus according to claim 1, wherein the sub-scanning includes movement corresponding to two or more movement directions on a plane on which the observation optical system moves relative to the array plate.
7. The scanning apparatus according to claim 6, wherein the sub-scanning includes movement in the first direction.
8. The scanning apparatus according to claim 1, further comprising an acquisition unit configured

to acquire information about the array plate, wherein the adjustment unit performs the adjustment based on the information about the array plate acquired by the acquisition unit.

**9.** The scanning apparatus according to claim 8, wherein the information about the array plate includes tilt information about the array plate as viewed from the first direction.

**10.** The scanning apparatus according to claim 9, wherein the tilt information about the array plate is calculated based on height information about the array plate acquired at least at two points.

**11.** The scanning apparatus according to claim 1, wherein the scanning unit moves the observation optical system and the array plate relative to each other based on information about a position of the observation optical system and information about a position of the array plate.

**12.** The scanning apparatus according to claim 1, wherein the adjustment unit performs the adjustment based on information about an imaging region from which the optical information is acquired and information about a position of the observation optical system.

**13.** The scanning apparatus according to claim 12, wherein in a case where the position of the observation optical system is outside the imaging region, the adjustment unit performs the adjustment.

**14.** The scanning apparatus according to claim 12, wherein the information about the imaging region is information input in advance by a user.

**15.** The scanning apparatus according to claim 11, further comprising a measurement unit configured to measure the position of the observation optical system, wherein the information about the position of the observation optical system is information acquired based on the position of the observation optical system measured by the measurement unit.

**16.** The scanning apparatus according to claim 11, further comprising a driving unit configured to move the observation optical system relative to the array plate, wherein the information about the position of the observation optical system is information acquired based on a signal for driving the driving unit.

**17.** The scanning apparatus according to claim 1, wherein the second direction is a direction perpendicular to the first direction.

**18.** The scanning apparatus according to claim 1, wherein the second direction is a direction that is not perpendicular to the first direction but is inclined relative to the first direction.

**19.** The scanning apparatus according to claim 1, wherein the array plate has a rectangular shape with a short side and a long side when viewed from the one surface, wherein the first direction is a direction parallel to the short side of the array plate, and wherein the second direction is a direction parallel to the long side of the array plate.

**20.** The scanning apparatus according to claim 1, wherein the array plate has a rectangular shape with a short side and a long side when viewed from the one surface, wherein the first direction is a direction parallel to the short side of the array plate, and wherein the second direction is a direction intersecting both the short side and the long side of the array plate.

**21.** The scanning apparatus according to claim 1, wherein the observation optical system is configured to radiate the primary light toward at least a portion of the plurality of spots and capture secondary light from the at least a portion of the plurality of spots.

**22.** A scanning method for causing an observation optical system to scan over an array plate including a plurality of spots on one surface, the method comprising: performing main scanning in which the observation optical system configured to radiate primary light toward the one surface to acquire optical information related to at least a portion of the plurality of spots moves relative to the array plate in a first direction and acquires the optical information and sub-scanning in which the observation optical system moves relative to the array plate in a second direction intersecting the first direction without acquiring the optical information; and adjusting a position of the observation optical system relative to the array plate in an optical axis direction of the primary light, wherein the adjusting performs the adjustment in a period of the sub-scanning by the scanning.



**23.** The scanning method according to claim 22, further comprising acquiring information about the array plate in advance prior to the scanning, wherein the adjusting performs the adjustment based on the acquired information about the array plate.

**24.** A storage medium storing a program for causing a computer to execute the scanning method according to claim 22.

---