

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287143

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

Leanse; Matthew

IN-EAR MONITOR APPARATUS

Abstract

An in-ear monitor apparatus includes: an electro-acoustic module; an internal sleeve; and a housing. The electro-acoustic module includes a front port configured to pass a front wave generated by an audio driver; a rear port configured to pass a back wave generated by the audio driver. The internal sleeve defines: a receptacle configured to receive and retain the electro-acoustic module; and a nozzle. The nozzle: extends between the receptacle and an audio outlet; and configured to pass the front wave from the receptacle to the audio outlet. The housing: is configured to contain the electro-acoustic module and the internal sleeve; cooperates with an external surface of the internal sleeve to define an internal back wave volume mechanically isolated from the nozzle by the internal sleeve; defines a back wave aperture configured to pass the back wave out of the housing.

Inventors: Leanse; Matthew (San Carlos, CA)

Applicant: Singularity Industries Inc. (San Carlos, CA)

Family ID: 96949821

Appl. No.: 19/076736

Filed: March 11, 2025

Related U.S. Application Data

us-provisional-application US 63563896 20240311

Publication Classification

Int. Cl.: H04R1/28 (20060101); H04R1/10 (20060101)

U.S. Cl.:

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This Application claims the benefit of U.S. Provisional Application No. 63/563,896, filed on 11 Mar. 2024, which is hereby incorporated in its entirety by this reference.

TECHNICAL FIELD

[0002] This invention relates generally to the field of electroacoustics and more specifically to a new and useful in-ear monitor apparatus in the field of electroacoustics.

Description

BRIEF DESCRIPTION OF THE FIGURES

[0003] FIGS. 1A, 1B and 1C are schematic representation of an in-ear monitor apparatus;
[0004] FIG. 2 is a schematic representation of an in-ear monitor apparatus;
[0005] FIG. 3 is a schematic representation of an in-ear monitor apparatus;
[0006] FIGS. 4A, 4B and 4C are schematic representations of an in-ear monitor apparatus;
[0007] FIGS. 5A, 5B and 5C are schematic representations of an in-ear monitor apparatus; and
[0008] FIGS. 6A, 6B 6C, 6D and 6E are schematic representations of an in-ear monitor apparatus.

DESCRIPTION OF THE EMBODIMENTS

[0009] The following description of embodiments of the invention is not intended to limit the invention to these embodiments but rather to enable a person skilled in the art to make and use this invention. Variations, configurations, implementations, example implementations, and examples described herein are optional and are not exclusive to the variations, configurations, implementations, example implementations, and examples they describe. The invention described herein can include any and all permutations of these variations, configurations, implementations, example implementations, and examples.

1. Apparatus

[0010] As shown in FIGS. 1A, 1B, and 1C, an in-ear monitor apparatus **100** includes: an electro-acoustic assembly **120**; an internal sleeve **140**; and a housing **160**.

[0011] The electro-acoustic assembly **120** includes: an audio driver **122** (e.g., side-firing micro-electromechanical system speaker); a printed circuit board **124**; and a connector **126** (e.g., a micro-miniature coaxial connector). The audio driver **122** includes a front port **123** configured to pass a front wave generated by the audio driver **122**. The printed circuit board **124** is coupled to the audio driver **122** and includes: a rear port **125** configured to pass a back wave generated by the audio driver **122**; and a set of solder pads arranged proximal the rear port **125**. The connector **126** is coupled to the set of solder pads and defines a relief: adjacent the rear port **125**; and configured to pass the back wave through the rear port **125**.

[0012] The internal sleeve **140** defines a receptacle **142** and a front volume **144** (or “duct”). The receptacle **142** is configured to receive and retain the electro-acoustic assembly **120** (e.g., via a press-fit, interference-fit). The front volume **144**: extends between the receptacle **142** and an audio outlet; and is configured to pass the front wave from the receptacle **142** to the audio outlet.

[0013] The housing **160** is configured to contain the electro-acoustic assembly **120** and the internal sleeve **140**. The housing **160** defines an input aperture configured to receive and locate the connector **126** proximal an input region of the housing **160**. The housing **160** also defines an output

aperture configured to: receive and locate the audio outlet of the internal sleeve **140** proximal an output region of the housing **160**; and locate proximal an ear of a user.

[0014] The housing **160** cooperates with an external surface of the internal sleeve **140** to define an internal back wave volume **162**: extending annularly about the internal sleeve **140**; and mechanically and acoustically isolated from the front volume **144** by the internal sleeve **140**.

[0015] The housing **160** further defines a back wave aperture **164**: opposite the audio outlet; intersecting the internal back wave volume **162**; and configured to pass the back wave from the internal back wave volume **162** to an exterior of the housing **160**.

2. Applications

[0016] Generally, an in-ear monitor apparatus **100** can function as a compact, low-profile wearable audio device configured to separate and contain acoustic waves (e.g., a front wave, a back wave) within distinct propagation paths to prevent or suppress destructive interference between these acoustic waves and maintain high-fidelity reproduction of an audio signal output by the in-ear monitor apparatus **100**.

[0017] More specifically, the in-ear monitor apparatus **100** can: define a front propagation path for a front wave generated by an audio driver **122** (e.g., a micro-electromechanical system speaker) toward an audio outlet; and define a back propagation path—isolated from the front propagation path—generated by the audio driver **122** toward back wave apertures to minimize destructive interference between the front wave and the back wave and maintain high-fidelity sound reproduction of an audio signal at the audio outlet.

[0018] The in-ear monitor apparatus **100** can include an electro-acoustic assembly **120** configured to: couple to an audio source (e.g., a tablet, a laptop); and generate acoustic waves (e.g., a front wave and a back wave) based on an electrical signal representative of an audio waveform (e.g., music) received from the audio source (e.g., via a cable assembly). The electro-acoustic assembly **120** can include an audio driver **122** (e.g., a micro-electromechanical system speaker) including a front port **123** (e.g., side slit port) configured to pass the front wave. Additionally, the electro-acoustic assembly **120** further includes a printed circuit board **124** coupled to the audio driver **122** and defining a rear port **125**—offset the front port **123**—configured to pass the back wave.

Furthermore, the in-ear monitor apparatus **100** can include an internal sleeve **140**: configured to receive and retain the electro-acoustic assembly **120**; and defining a front volume **144** to pass the front wave generated at the electro-acoustic assembly **120** toward an audio outlet.

[0019] Furthermore, the in-ear monitor apparatus **100** can include a housing **160** configured to conform to (or “fit within”) an ear of a user and locate the audio outlet of the internal sleeve **140** proximal an ear canal of the user. More specifically, the housing **160**: contains the electro-acoustic assembly **120** and the internal sleeve **140**; defines back wave apertures arranged opposite the audio outlet; and cooperates with an external surface of the internal sleeve **140** to define an internal back wave volume for passage of the back wave from the electro-acoustic assembly **120** towards the back wave apertures. As the back wave propagates through the internal back wave volume **162**, the back wave reflects off the internal surface of the housing **160** and the external surface of the internal sleeve **140** resulting in diffusive wave interactions to: dissipate acoustic energy of the back wave and minimize interference between the back wave and the front wave; and/or substantially egress the back wave from the in-ear monitor apparatus entirely (e.g., via the back wave aperture).

[0020] Therefore, the in-ear monitor apparatus **100** can maintain acoustic isolation between the front wave and the back wave—generated at the electro-acoustic assembly **120**—by defining independent propagation paths within a housing **160** that: impedes pressure variations within the internal back wave volume to support physical excursion of radiating surfaces of the audio driver in proportion to an input signal supplied to the audio driver **122**; mitigates phase distortion effects that can induce destructive modulation of the audio signal at the audio outlet; and passes the back wave out of the housing (e.g., via the back wave apertures) to prevent residual acoustic energy from re-entering the front volume **144** and interfering with propagation of the front wave.

3. Electro-Acoustic Assembly+Acoustic Wave Generation

[0021] Generally, the in-ear monitor apparatus **100** includes an electro-acoustic assembly **120** configured to: generate acoustic waves (e.g., front wave, back wave) that represent an audio signal (e.g., music, live audio feed); and isolate these acoustic waves along discrete propagation paths to minimize interference between these acoustic waves and maintain high-fidelity sound reproduction of the audio signal.

[0022] In one implementation, the electro-acoustic assembly **120** includes a micro-electromechanical system speaker configured to generate acoustic waves in response to an electrical input signal, such as from an audio source (e.g., tablet, laptop). More specifically, the micro-electromechanical system speaker can emit a front wave corresponding to an audio signal (e.g., music) from a front port **123** of an acoustic chamber of the micro-electromechanical system speaker. In this implementation, the electro-acoustic assembly **120** further includes a printed circuit board **124**: coupled to the micro-electromechanical system speaker; and defining a rear port **125** (e.g., a set of apertures) configured to pass a back wave—generated as an acoustic pressure wave resulting from diaphragm displacement within the acoustic chamber—toward an exterior of the electro-acoustic assembly **120**.

[0023] Furthermore, the electro-acoustic assembly **120** can include a connector **126** (e.g., a micro-miniature coaxial cable): coupled to solder pads at the printed circuit board **124**; defining a relief proximal the rear port **125** for unobstructed passage of the back wave output from the rear port **125**; and configured to interface with a cable (e.g., coaxial cable) that supplies the audio signal—such as from the audio source—to the micro-electromechanical system speaker via the solder pads.

[0024] In one example, the micro-electromechanical system speaker includes a front port **123** (e.g., a slit) arranged at a lateral side of the micro-electromechanical system speaker. In this example, the printed circuit board **124**: is coupled to a bottom end of the enclosure; and defines rear port **125s** proximal a rear side of the micro-electromechanical system speaker configured to pass the back wave toward an exterior of the electro-acoustic assembly **120**. Additionally, the connector **126** defines a demi-lune relief adjacent to the rear port **125** to maintain an open pathway for back wave propagation from the micro-electromechanical system speaker.

[0025] In another implementation, the electro-acoustic assembly **120** includes the audio driver **122** mechanically and electrically coupled to the connector **126**, such as rigidly coupled to the connector **126**, coupled parallel to the connector **126**, directly coupled to the connector **126**, and/or indirectly (e.g., via a printed circuit board) to the connector **126**. In this implementation, the audio driver **122** includes: the front port **123**; and the rear port **125**.

[0026] Therefore, the electro-acoustic assembly **120** can define structural features that delineate distinct and non-interfering propagation paths for the front wave and the back wave generated by an audio driver **122** (e.g., a micro-electromechanical system speaker) to: minimize destructive interference between the front wave and the back wave; and maintain high-fidelity sound reproduction of an audio signal supplied to the electro-acoustic assembly **120**.

3.1 Dual Drivers

[0027] In one implementation, the electro-acoustic assembly **120** includes a set of audio drivers **122** (e.g., identical drivers, a low-frequency driver and a high-frequency driver) configured to generate acoustic waves (e.g., front waves, back waves) based on a supplied audio signal. In this implementation, the electro-acoustic assembly **120** can implement the structure described above to define exclusive propagation paths for these acoustic waves.

4. Internal Sleeve: Front Volume+Back Wave Passage

[0028] Generally, the in-ear monitor apparatus **100** further includes an internal sleeve **140** configured to shape and isolate acoustic waves (e.g., a front wave, a back wave) output from the electro-acoustic assembly **120** along corresponding propagation paths to maintain wave integrity and suppress unintended dispersion of acoustic energy.

[0029] In one implementation, the internal sleeve **140** defines: a receptacle **142** configured to

receive and retain the electro-acoustic assembly **120**; a front volume **144** (e.g., a tapered front volume **144**) extending between the receptacle **142** and the audio outlet (or “sound bore”); and a rear port **125** relief (e.g., aperture) arranged proximal the rear port **125** of the printed circuit board **124**. In this implementation, the front volume **144** is configured to guide the front wave generated at the electro-acoustic assembly **120** along a controlled propagation path through the receptacle **142** and towards the audio outlet. Additionally, the rear port **125** relief of the internal sleeve **140** cooperates with the relief of the connector **126** to define a passage configured to pass the back wave generated at the electro-acoustic assembly **120** toward an exterior of the internal sleeve **140**. [0030] Furthermore, the front volume **144** can further include an acoustic filter (or “damping element”) configured to regulate a frequency response of the front wave by modifying airflow resistance and attenuating resonant peaks within the front volume **144**.

[0031] In one example, the front volume **144**: aligns with the front port **123** on the lateral side of the audio driver **122** to maintain a direct acoustic pathway from the receptacle **142** to the audio outlet; defines a contoured passage of a gradually constricting cross-section configured to reduce distortion and maintain clarity of the front wave propagating through the front volume **144** for high-fidelity acoustic reproduction of an audio signal at the audio outlet. In this example, the rear port **125** relief: is arranged on a bottom end of the internal sleeve **140** proximal the rear port **125** of the electro-acoustic assembly **120**; cooperates with the relief of the connector **126** to define a duct (or “passage”) aligned with the rear port **125** configured to pass the back wave toward the exterior of the internal sleeve **140**; and defines a contoured boundary that shapes wave characteristics (e.g., acoustic impedance matching, wave reflection control) of the back wave within the duct.

[0032] Therefore, the internal sleeve **140** defines dedicated pathways within the internal sleeve **140** to isolate propagation of the front wave within the front volume **144** from propagation of the back wave toward the exterior of the internal sleeve **140**. Thus, the internal sleeve **140** can preserve acoustic fidelity of the front wave for reproduction of an audio signal at the audio outlet.

5. Housing

[0033] Generally, the in-ear monitor apparatus **100** further includes a housing **160** configured to: contain (or “house”) the electro-acoustic assembly **120** and the internal sleeve **140**; and cooperate with the internal sleeve **140** to define an internal back wave volume **162** for dissipation of the back wave within the housing **160** to reduce interference between the back wave and the front wave.

5.1 Internal back Wave Volume

[0034] In one implementation, the housing **160** includes an internal surface that cooperates with the external surface of the internal sleeve **140** to define an internal back wave volume **162** extending annularly about the internal sleeve **140**. Accordingly, the internal sleeve **140** can then maintain propagation of the back wave through this internal back wave volume **162**. As the back wave propagates through the internal back wave volume **162**, the back wave reflects off the internal surface of the housing **160** and the external surface of the internal sleeve **140** resulting in diffusive wave interactions to dissipate acoustic energy of the back wave and minimize interference between the back wave and the front wave. More specifically, the internal surface of the housing **160** and the external surface of the internal sleeve **140** define an acoustic boundary about an air gap configured to: attenuate acoustic energy (e.g., amplitude) of the back wave as the back wave interacts with impedance transitions at the internal surface of the housing **160** and the external surface of the internal sleeve **140**; induce a phase cancellation effect through diffusive wave interactions that disrupt coherent reflections of the back wave; and maintain pressure equalization by distributing acoustic pressure variations of the back wave within the internal back wave volume **162**.

[0035] In one example, the housing **160** includes a curved internal surface that cooperates with a curved external surface of the internal sleeve **140** to exclude internal parallel surfaces and define an internal back wave volume **162** extending annularly about the internal sleeve **140**. The annular surfaces within the housing **160** are configured to disrupt uniform wavefront reflections of the back

wave to reduce formation of standing waves and minimize reinforcement of frequencies interfering with propagation of the front wave within the front volume **144**.

[0036] In another example, the external surface of the internal sleeve **140** cooperates with the internal surface of the housing **160** to form an internal back wave volume **162** that incorporates a Helmholtz resonator structure configured to regulate acoustic pressure and control resonance of the back wave within the housing.

[0037] Therefore, the housing **160** cooperates with the internal sleeve **140** to disrupt and scatter acoustic reflections of the back wave propagating through the internal back wave volume to: maintain acoustic separation between the back wave from the front wave propagating through the front volume **144** of the internal sleeve **140**; and maintain a frequency response of the front wave propagating through the front volume **144** of the internal sleeve **140**.

5.2 Venting+Back Wave

[0038] In one implementation, the housing **160** defines a set of back wave apertures **164** arranged about a periphery of the housing **160**—opposite from the audio outlet—and configured to minimize pressure fluctuations within the internal back wave volume **162**. In this implementation, each back wave aperture defines an acoustic pathway that intersects the internal back wave volume **162** of the housing **160** to an external environment in order to dissipate acoustic energy of the back wave—propagating within the internal back wave volume **162**—by releasing residual acoustic pressure to prevent standing wave formations within the housing **160**. As the back wave propagates through the internal back wave volume **162**, the back wave: transitions impedance boundaries at the back wave aperture; propagates to an exterior of the housing **160** to reduce internal reflections of the back wave within the housing **160**; and exhibits rapid pressure diffusion to minimize reinforcement of uncontrolled frequencies of the back wave within the housing **160**.

[0039] In one example, the set of back wave apertures **164**: define a series of elongated slots or circular perforations to regulate airflow and acoustic wave dispersion from the internal back wave volume **162**; are arranged on the housing **160** opposite the audio outlet to pass the back wave away from the front wave path; and configured to control acoustic impedance at a boundary of each back wave aperture to manage wave dissipation within the internal back wave volume **162**.

[0040] In another example, as described above, the external surface of the internal sleeve **140** cooperates with the internal surface of the housing **160** to form an internal back wave volume **162** that incorporates a Helmholtz resonator structure configured to regulate acoustic pressure and control resonance of the back wave within the housing **160**. In this example, the set of back wave apertures **164** define a tunned acoustic pathway configured to regulate resonance characteristics and manage dissipation of the back wave.

[0041] Therefore, the set of back wave apertures **164** define propagation paths for dispersing the back wave along a trajectory opposite to propagation of the front wave (i.e., at the audio outlet) to prevent destructive interference between the front wave and the back wave.

5.3 Wires+Audio Signal Reproduction

[0042] In one implementation, the housing **160** defines structural features configured to support coupling between electrical components and an ear (e.g., a right ear, a left ear) of a user. In this implementation, the housing **160** can define an input aperture: configured to receive and locate the connector **126** proximal to an input region of the housing **160**; including a recessed mounting interface that stabilizes the connector **126** during insertion and maintains electrical coupling to the electro-acoustic assembly **120**; and configured to constrain cable positioning to prevent strain on internal electrical connections and minimize mechanical stress at the mounting interface.

Additionally, the housing **160** can define an output aperture: configured to receive and locate the audio outlet of the internal sleeve **140** proximal to an output region of the housing **160**; including a contoured surface profile that conforms to the ear of the user to maintain stability of the in-ear monitor apparatus **100** at the ear of the user; and configured to position the audio outlet proximal the ear of the user for direct transmission of the front wave toward into an ear canal of the user.

[0043] In one example, the input aperture: is arranged at a bottom end of the housing **160**; and locates a primary connector **126** (e.g., a female micro-miniature coaxial connector) of the electro-acoustic assembly **120** that is configured to couple a secondary connector (e.g., a male micro-miniature coaxial connector) of the cable assembly. Accordingly, an audio source can then transmit an electrical signal representative of an audio waveform (e.g., music) to the electro-acoustic assembly **120** via the cable assembly. An audio driver **122** of the electro-acoustic assembly **120** can then generate a front wave and a back wave based on this electrical signal. In this example, the output aperture is arranged along a lateral side of the housing **160**; and is configured to locate the audio outlet of the internal sleeve **140** proximal the ear of the user.

[0044] Accordingly, the housing **160** and the internal sleeve **140** cooperate to: isolate the back wave propagating within the housing **160** from the front wave propagating within the front volume **144**; and maintain high-fidelity reproduction of the audio waveform at the ear of the user.

6. “Ship-in-a-Barrel” Assembly

[0045] In one implementation, the housing **160** includes: a primary housing section; and a secondary housing section that couples the primary housing section to contain the electro-acoustic assembly **120** and the internal sleeve **140**.

[0046] For example, the primary housing section includes: the input aperture arranged at an input region of the primary housing section and configured to locate the connector **126** of the electro-acoustic assembly **120**; and inner threads arranged about a coupling region of the primary housing section. Additionally, the secondary housing section includes: the output aperture arranged at the output region of the secondary housing section and configured to locate the audio outlet of the internal sleeve **140**; and outer threads configured to couple the inner threads at the coupling region of the primary housing section to locate the electro-acoustic assembly **120** and the internal sleeve **140** within the housing **160**.

[0047] During assembly of the in-ear monitor apparatus **100**, the electro-acoustic assembly **120** and the internal sleeve **140** are inserted into the primary housing section to: locate the connector **126** of the electro-acoustic assembly **120** proximal the input region of the primary housing section; and couple the internal sleeve **140** to retention features arranged within the primary housing section. The secondary housing section is then coupled to the primary housing section to: rigidly locate the electro-acoustic assembly **120** and the internal sleeve **140** within the housing **160**; and locate the audio output proximal the output aperture of the housing **160**.

[0048] Therefore, the in-ear monitor apparatus **100** can include a two-part housing **160** defining interlocking structural features that rigidly locate internal components (i.e., the electro-acoustic assembly **120**, the internal sleeve **140**) within the two-part housing **160** with minimal fastening elements.

6.1 Acoustic Seal

[0049] In one implementation, the internal sleeve **140**: can be formed (e.g., via three-dimensional printing) of an elastomeric material exhibiting damping characteristics that absorb mechanical vibrations, such as resulting from propagation of the back wave; and defines a seal about the audio driver **122** of the electro-acoustic assembly **120** to block acoustic leakage—from the audio driver **122** at electro-acoustic assembly **120**—that can destructively interfere with the front wave propagating through the front volume **144**. Additionally or alternatively, the internal sleeve **140** can include a sealant (e.g., fluoropolymer grease) cooperating with the elastomeric material to block acoustic leakage from the audio driver **122**.

[0050] In one example, the internal sleeve **140** defines a unitary elastomeric element: configured to envelop the electro-acoustic assembly **120** and form a continuous barrier against acoustic leakage; defining apertures that permit the front wave to propagate through the front volume **144** and the back wave to vent through the rear port **125**; and exhibiting elastomeric characteristics to absorb mechanical vibrations from the electro-acoustic assembly **120**, isolate the electro-acoustic assembly **120** from shock associated with abusive handling of the in-ear monitor apparatus **100**, and prevent

distortion of the front wave propagating through the front volume **144**.

[0051] Therefore, the internal sleeve **140** can: minimize acoustic leakage from the audio driver **122** of the electro-acoustic assembly **120** to maintain integrity of the front wave and the back wave; and cooperate with the electro-acoustic assembly **120** to define distinct propagation paths for the front wave and the back wave to block destructive interference and maintain fidelity of audio output at the audio outlet.

6.2 Insulating Ring

[0052] In one implementation, the in-ear monitor apparatus **100** includes an insulating ring configured to support mechanical coupling and electrical isolation between the electro-acoustic assembly **120** and the housing **160**. The insulating ring: forms a sealed interface about the connector **126** of the electro-acoustic assembly **120**; cooperates with an undercut taper (or “bore”) at the input region of the housing **160** to form an interference fit that rigidly retains and aligns the insulating ring to the housing **160**; and is configured to block propagation of the back wave to the input region of the housing **160**. More specifically, the insulating ring is configured to: maintain a nominal seal between the electro-acoustic assembly **120** and the housing **160** to minimize acoustic leakage of the back wave; and support pressure stabilization within the internal back wave volume by blocking airflow through the input region of the housing **160**.

[0053] Accordingly, the insulating ring can define a dielectric barrier between the housing **160** and the electro-acoustic assembly **120** that: maintains electrical insulation under mechanical stress between the housing **160** and the electro-acoustic assembly **120**; and maintains electrical signal transmission to the electro-acoustic assembly **120**.

6.3 Bridge

[0054] In one implementation, the in-ear monitor apparatus **100** includes a bridge **166** configured to support stability and alignment of the electro-acoustic assembly **120** and the internal sleeve **140** within the housing **160**. In this implementation, the internal sleeve **140** includes a slot (or “bore”) configured to receive and retain the bridge **166**. The bridge **166** extends from the internal sleeve **140** and is configured couple to a bore arranged within the housing **160** to: constrain and structurally reinforce the electro-acoustic assembly **120** and the internal sleeve **140** within the housing **160**, such as during application of external forces at the connector **126**; maintain alignment of the electro-acoustic assembly **120** within the housing **160**.

[0055] During assembly of the in-ear monitor apparatus **100**, the bridge **166**: locates within the bore of the housing **160** to form a mechanical interface between the housing **160** sections; and bends under shear stress during assembly of the two-part housing **160** to stabilize and reinforce the electro-acoustic assembly **120** and the internal sleeve **140** within the housing **160**, such as to resist deflection under external forces (e.g., cable insertion, incidental torque, handling forces). The bridge **166** is configured to apply a compressive force to the housing **160** and the internal sleeve **140** to: compress the connector **126** against the insulating ring to acoustically seal the input aperture of the housing **160** and prevent acoustic leakage of the back wave from the internal back wave volume **162**; compress the internal sleeve **140** against the housing **160** to acoustically seal the output aperture of the housing **160** and prevent acoustic leakage of the back wave from the internal back wave volume **162**; and rigidly retain the electro-acoustic assembly **120** and the internal sleeve **140** within the housing **160** to prevent displacement of the electro-acoustic assembly **120** and the internal sleeve **140** during operation of the in-ear monitor apparatus **100**.

[0056] Accordingly, the bridge **166** cooperates with the internal sleeve **140** and the housing **160** to: diffuse mechanical vibrations from the electro-acoustic assembly **120**; reduce parasitic resonances by stabilizing the contact points between internal components within the housing **160**; and minimize transmission of external shocks to the electro-acoustic assembly **120** to preserve consistent acoustic output at the audio outlet.

[0057] Therefore, the bridge **166**: constrains movement of internal components within the housing **160** by maintaining positional integrity under external mechanical loads to prevent displacement of

these internal components that can result in disruption of wave propagation and/or electrical continuity; and forms a localized damping interface that regulates vibrational energy transfer within the housing **160** to mitigate uncontrolled oscillations that can result in degradation of signal fidelity at the audio outlet.

7. Variation: Ventless Housing

[0058] In one variation, the in-ear monitor apparatus **100** excludes back wave apertures and defines structural features configured to regulate back wave propagation within a substantially enclosed internal back wave volume **162** of a housing **160**. In this variation, the housing **160**: cooperates with the internal sleeve **140** to define an internal back wave volume **162** that fully encloses the back wave to prevent uncontrolled acoustic leakage; includes a contoured internal surface to scatter back wave reflections and minimize standing wave formations within the internal back wave volume **162**; and is configured to regulate internal air displacement and maintain acoustic stability of the back wave. Additionally, the housing **160** can: include an internal damping layer (e.g., porous foam, elastomeric baffles) configured to absorb acoustic energy and mitigate excessive wave reinforcement of the back wave; include a damping material adjacent to the rear port **125** of the electro-acoustic assembly **120** to attenuate back wave amplitude; implement an enclosure structure to minimize resonance buildup of the back wave within the housing **160**. As the back wave propagates through the internal back wave volume **162**, the back wave: reflects off the contoured internal surface of the housing **160** and the external surface of the internal sleeve **140** to scatter reflections of the back wave; transitions across impedance boundaries formed by damping layers and geometry of the housing **160** to gradually dissipate acoustic energy of the back wave; and transition across the damping material arranged adjacent to the rear port **125** of the electro-acoustic assembly **120** to attenuate residual wave amplitude of the back wave.

[0059] Therefore, the in-ear monitor apparatus **100** can include a housing **160** defining a fully enclosed internal back wave volume **162** configured to: contain and dissipate acoustic energy of the back wave without venting the back wave toward an exterior fourth the housing **160**; and maintain pressure equilibrium within the housing **160** while preventing acoustic interference between the back wave and the front wave.

7.1 Variation: Plastic Housing

[0060] In one variation, the housing **160** includes: a primary housing section (e.g., a plastic housing section); and a secondary housing section (e.g., plastic housing section) bonded (e.g., adhesively bonded) to the primary housing section to contain the electro-acoustic assembly **120** and internal sleeve **140**. In this variation, the primary housing **160** is bonded to the secondary housing **160** to: form a continuous external surface; and define an internal cavity that conforms to the external geometry of the internal sleeve **140** to maintain acoustic isolation between the front wave and the back wave.

[0061] In this variation, during assembly of the in-ear monitor apparatus **100**, the electro-acoustic assembly **120** and the internal sleeve **140** are seated within a recessed cavity of a primary housing section. The secondary housing **160** is then aligned with a bonding region of the primary housing section to: enclose the electro-acoustic assembly **120** and the internal sleeve **140**; and define the internal back wave volume **162** configured to pass the back wave. Additionally, an adhesive material is applied about the bonding region of the primary housing section and the secondary housing section to: form a seamless external enclosure; and form an acoustic seal between the housing **160** and the internal sleeve **140** to block acoustic leakage of the back wave from interfering with the front wave.

[0062] Therefore, the in-ear monitor apparatus **100** can include an adhesively bonded housing **160**—containing the electro-acoustic assembly **120** and the internal sleeve **140**—that: maintains an internal back wave volume **162** for controlled dissipation of a back wave; and eliminates mechanical discontinuities of the housing **160** that can result in disruption of acoustic wave propagation.

8. Disclaimer

[0063] The systems and methods described herein can be embodied and/or implemented at least in part as a machine configured to receive a computer-readable medium storing computer-readable instructions. The instructions can be executed by computer-executable components integrated with the application, applet, host, server, network, website, communication service, communication interface, hardware/firmware/software elements of a user computer or mobile device, wristband, smartphone, or any suitable combination thereof. Other systems and methods of the embodiment can be embodied and/or implemented at least in part as a machine configured to receive a computer-readable medium storing computer-readable instructions. The instructions can be executed by computer-executable components integrated by computer-executable components integrated with apparatus **100e**s and networks of the type described above. The computer-readable medium can be stored on any suitable computer readable media such as RAMs, ROMs, flash memory, EEPROMs, optical devices (CD or DVD), hard drives, floppy drives, or any suitable device. The computer-executable component can be a processor but any suitable dedicated hardware device can (alternatively or additionally) execute the instructions.

[0064] As a person skilled in the art will recognize from the previous detailed description and from the figures and claims, modifications and changes can be made to the embodiments of the invention without departing from the scope of this invention as defined in the following claims.

Claims

1. An in-ear monitor apparatus comprising: an electro-acoustic module comprising: an audio driver comprising a front port configured to pass a front wave generated by the audio driver; a printed circuit board coupled to the audio driver and comprising: a rear port configured to pass a back wave generated by the audio driver to an internal back wave volume; and a set of solder pads arranged proximal the rear port; and a connector coupled to the set of solder pads; an internal sleeve defining: a receptacle configured to receive and retain the electro-acoustic module; and a nozzle: extending between the receptacle and an audio outlet; and configured to pass the front wave from the receptacle to the audio outlet; and a housing: configured to contain the electro-acoustic module and the internal sleeve; defining: an input aperture configured to receive and locate the connector proximal an input region of the housing; and an output aperture configured to: receive and locate the audio outlet of the internal sleeve proximal an output region of the housing; and locate proximal an ear of a user; cooperating with an external surface of the internal sleeve to define the internal back wave volume: extending annularly about the internal sleeve; and mechanically isolated from the nozzle by the internal sleeve; and defining a back wave aperture: opposite the audio outlet; intersecting the internal back wave volume; and configured to pass the back wave out of the housing.

2. The in-ear monitor apparatus of claim 1, wherein the connector defines a relief: adjacent the rear port; and configured to pass the back wave from the rear port to the internal back wave volume.

3. An in-ear monitor apparatus comprising: an electro-acoustic module comprising: an audio driver comprising: a front port configured to pass a front wave generated by the audio driver; and a rear port configured to pass a back wave generated by the audio driver to an internal back wave volume; a connector coupled to the audio driver; an internal sleeve defining: a receptacle configured to receive and retain the electro-acoustic module; and a nozzle: extending between the receptacle and an audio outlet; and configured to pass the front wave from the receptacle to the audio outlet; and a housing: configured to contain the electro-acoustic module and the internal sleeve; defining: an input aperture configured to receive and locate the connector proximal an input region of the housing; and an output aperture configured to: receive and locate the audio outlet of the internal sleeve proximal an output region of the housing; and locate proximal an ear of a user; cooperating with an external surface of the internal sleeve to define the internal back wave volume: extending

annularly about the internal sleeve; and mechanically isolated from the nozzle by the internal sleeve; and text missing or illegible when filed
