

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12407032
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Wang; Wenwei et al.

Electric vehicle and battery system

Abstract

The present application provides an electric vehicle and a battery system. The electric vehicle comprises: a frame; a first power consumption unit and a second power consumption unit, the first power consumption unit and the second power consumption unit being connected to the frame; and a battery system, comprising a first power supply unit and a second power supply unit, the first power supply unit and the second power supply unit each comprising at least one battery pack, the first power supply unit supplying power to the first power consumption unit, and the second power supply unit supplying power to the second power consumption unit, wherein the at least one battery pack can supply power to a handheld tool.

Inventors:	Wang; Wenwei (Changzhou, CN), Wei; Qunli (Changzhou, CN), Xue; Jiafu (Changzhou, CN), Shi; Dongdong (Changzhou, CN), Chen; Hui (Changzhou, CN), Zhao; Peng (Changzhou, CN), Shi; Qinghua (Changzhou, CN)
Applicant:	Globe (Jiangsu) Co. Ltd. (Changzhou, CN)
Family ID:	77890176
Assignee:	Globe (Jiangsu) Co. Ltd. (N/A, CN)
Appl. No.:	17/913564
Filed (or PCT Filed):	March 25, 2021
PCT No.:	PCT/CN2021/083071
PCT Pub. No.:	WO2021/190612
PCT Pub. Date:	September 30, 2021

Prior Publication Data

Document Identifier	Publication Date
---------------------	------------------

Foreign Application Priority Data

CN	202010222174.8	Mar. 26, 2020
CN	202010222359.9	Mar. 26, 2020
CN	202020399165.1	Mar. 26, 2020
CN	202010227225.6	Mar. 27, 2020
CN	202010341659.9	Apr. 27, 2020
CN	202010489646.6	Jun. 02, 2020
CN	202011107782.0	Oct. 16, 2020
CN	202110048184.9	Jan. 14, 2021

Publication Classification

Int. Cl.: **H01M10/44** (20060101); **A01D34/66** (20060101); **B60L1/00** (20060101); **B60L50/64** (20190101); **H01M50/249** (20210101); A01D34/78 (20060101); A01D69/02 (20060101); A01D101/00 (20060101)

U.S. Cl.:

CPC **H01M10/441** (20130101); **B60L1/00** (20130101); **B60L50/64** (20190201); **H01M50/249** (20210101); A01D34/66 (20130101); A01D34/78 (20130101); A01D69/02 (20130101); A01D2101/00 (20130101); H01M2220/20 (20130101)

Field of Classification Search

CPC: H01M (10/441); H01M (50/249); B60L (50/64); B60L (1/00); A01D (34/66); A01D (34/178); A01D (69/02)

USPC: 180/68.5

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
8575800	12/2012	Fox	310/157	A01D 69/02
9840143	12/2016	Keller	N/A	F16H 57/04
10426084	12/2018	Ito	N/A	A01D 34/78
10882509	12/2020	Books	N/A	B60K 6/448
11199798	12/2020	Morishita	N/A	G03G 15/5004
11942807	12/2023	Wang	N/A	H02J 7/00304
2003/0037525	12/2002	Iida	56/11.9	A01D 34/6812
2004/0021437	12/2003	Maslov	318/400.01	H02K 1/141
2005/0087375	12/2004	Steele et al.	N/A	N/A
2010/0307844	12/2009	Peters	N/A	N/A
2012/0186887	12/2011	Moriguchi	180/65.1	B60L 58/15

2012/0228946	12/2011	Sim et al.	N/A	N/A
2012/0317949	12/2011	Abe	56/11.9	H01H 3/20
2014/0084689	12/2013	Jung et al.	N/A	N/A
2014/0137528	12/2013	Schygge	180/14.1	A01D 34/78
2014/0165524	12/2013	Schygge	180/62	B60L 1/16
2016/0183451	12/2015	Conrad	56/10.2 R	A01D 34/66
2017/0263914	12/2016	Ito et al.	N/A	N/A
2018/0118011	12/2017	Grace	N/A	B60L 58/26
2018/0303027	12/2017	Koike	N/A	B60L 50/51
2019/0124837	12/2018	Ito	N/A	A01D 69/02
2019/0152342	12/2018	Shen	N/A	B60L 50/64
2019/0199118	12/2018	Hoppel et al.	N/A	N/A
2019/0381988	12/2018	Matsuda	N/A	B60L 58/12

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
1074867	12/1992	CN	N/A
2886896	12/2006	CN	N/A
101128287	12/2007	CN	N/A
102082307	12/2010	CN	N/A
102122740	12/2010	CN	N/A
102145691	12/2010	CN	N/A
201961148	12/2010	CN	N/A
202712292	12/2012	CN	N/A
203120457	12/2012	CN	N/A
103283403	12/2012	CN	N/A
103518487	12/2013	CN	N/A
104167770	12/2013	CN	N/A
203575118	12/2014	CN	N/A
105172988	12/2014	CN	N/A
105552260	12/2015	CN	N/A
105799549	12/2015	CN	N/A
106210208	12/2015	CN	N/A
106891753	12/2016	CN	N/A
107054451	12/2016	CN	N/A
107093918	12/2016	CN	N/A
108146294	12/2017	CN	N/A
110228369	12/2018	CN	N/A
110827495	12/2019	CN	N/A
110834558	12/2019	CN	N/A
210617861	12/2019	CN	N/A
111296044	12/2019	CN	N/A
111313503	12/2019	CN	N/A
212573554	12/2020	CN	N/A
2332760	12/2010	EP	N/A
2002078214	12/2001	JP	N/A
2016166864	12/2015	JP	N/A
6300127	12/2015	JP	N/A
2016206685	12/2015	JP	N/A
2019137104	12/2018	JP	N/A

OTHER PUBLICATIONS

International Search Report for related International Patent Application No. PCT/CN2021/083071 issued on Jul. 6, 2021 and English translation. cited by applicant

Primary Examiner: Phan; Hau V

Attorney, Agent or Firm: Shumaker, Loop & Kendrick, LLP

Background/Summary

TECHNICAL FIELD

(1) The invention relates to the technical field of garden equipment, in particular to an electric vehicle and a battery system.

BACKGROUND TECHNIQUE

(2) The type of battery pack used for lithium-ion mounted garden tools currently on the market is usually a large battery pack or a combination of several small battery packs. The output energy is used for walking, mowing or other garden tools at the same time. Accessory use. With this setting, if one battery pack or one of several battery pack combinations is damaged, the power supply of the whole machine will be abnormal and it will not be able to drive, and then the operator will not be able to operate the machine outdoors; the garden tools will be sent to the designated transportation point or In the process of maintenance, the machine can only be transported by labor or other tools, which damages the user experience of garden tools.

SUMMARY OF THE INVENTION

(3) The present disclosure provides an electric vehicle, including: frame; A first power consuming unit and a second power consuming unit, the first power consuming unit and the second power consuming unit are connected to the rack; and A battery system includes a first power supply unit and a second power supply unit, the first power supply unit and the second power supply unit each include at least one battery pack, and the first power supply unit supplies power to the first power consumption unit, The second power supply unit supplies power to the second power consumption unit; Wherein, at least one of the battery packs can supply power to the hand-held tool.

(4) The present disclosure provides a battery system, including: The first power supply unit supplies power to the first power consumption unit; and The second power supply unit supplies power to the second power consumption unit; Wherein, the first power supply unit and the second power supply unit both include at least one battery pack, and at least one of the battery packs can supply power to the handheld tool.

(5) In summary, the present disclosure proposes an electric vehicle and a battery system. By providing a battery system on the electric vehicle, the battery system can include different power supply units, and different power supply units can supply power to different power consumption units, thus avoiding the abnormal use of the battery system is caused by the damage of the battery pack in the single power supply unit, thereby making the electric vehicle convenient to use, with high use efficiency and good user experience.

Description

DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a schematic diagram of the three-dimensional structure of the mounted electric tool of the present invention.
- (2) FIG. 2 is a schematic view of another perspective three-dimensional structure of the mount-type electric tool shown in FIG. 1.
- (3) FIG. 3 is a schematic diagram of the cooperation of the driving mechanism and the operating mechanism.
- (4) FIG. 4 is a schematic diagram of the structure of the first handle.
- (5) FIG. 5 is a schematic diagram of the cooperation between the support arm and the first brake line.
- (6) FIG. 6 is a partial enlarged view of FIG. 3.
- (7) FIG. 7 is a three-dimensional schematic diagram of the electric vehicle of the present invention.
- (8) FIG. 8 is a perspective schematic view of the electric vehicle shown in FIG. 7 from another angle.
- (9) FIG. 9 is a schematic diagram of the bottom of the electric vehicle shown in FIG. 7.
- (10) FIG. 10 is a perspective schematic view of the electric vehicle described in FIG. 7 with the working mechanism removed.
- (11) FIG. 11 is a perspective schematic view from another angle of the electric vehicle shown in FIG. 7 with the working mechanism removed.
- (12) FIG. 12 is a perspective schematic view of the electric vehicle shown in FIG. 7 with the working mechanism and housing removed.
- (13) FIG. 13 is a three-dimensional schematic diagram of a rear drive assembly and a pivotal assembly.
- (14) FIG. 14 is a perspective schematic view of the rear drive assembly and the pivotal assembly from another angle.
- (15) FIG. 15 is a three-dimensional schematic diagram of the electric tool of the present invention.
- (16) FIG. 16 is a schematic structural view of FIG. 15 omitting the seat assembly.
- (17) FIG. 17 is a schematic diagram of the structure of the working assembly in FIG. 15.
- (18) FIG. 18 is a schematic diagram of the structure of the driving wheel assembly in FIG. 15.
- (19) FIG. 19 is a schematic diagram of the structure of the distributed battery management system in FIG. 16.
- (20) FIG. 20 is a three-dimensional schematic diagram of a hand-held garden tool suitable for the battery pack in FIG. 19.
- (21) FIG. 21 is a working principle diagram of the distributed battery management system in FIG. 19 during charging.
- (22) FIG. 22 is a control principle diagram of the electric tool in FIG. 15.
- (23) FIG. 23 is a structural block diagram of the energy management system of the present invention.
- (24) FIG. 24 is a control principle diagram of the energy management system of the present invention.
- (25) FIG. 25 is a flowchart of the energy management method of the present invention.
- (26) FIG. 26 is a structural block diagram of the energy management method of step S3 in FIG. 25.
- (27) FIG. 27 is a schematic diagram of the structure of the electric tool of the present invention.
- (28) FIG. 28 is a schematic structural view of the electric tool of which part of the structure is omitted in FIG. 27.
- (29) FIG. 29 is a schematic diagram of the disassembly of the tool system in FIG. 27.
- (30) FIG. 30 is a schematic structural diagram of the tool system in FIG. 27 from another angle.
- (31) FIG. 31 is a schematic diagram of the structure of the tool assembly in FIG. 27.
- (32) FIG. 32 is a schematic diagram of the structure of the battery assembly in FIG. 27.

- (33) FIG. **33** is a control principle diagram of the electric tool in FIG. **27**.
- (34) FIG. **34** is a schematic diagram of the structure of the electric tool of the present invention.
- (35) FIG. **35** is a schematic diagram of the circuit between the power supply component and the drive component of the present invention.
- (36) FIG. **36** is a block diagram of the connection structure of the electric energy management unit, the power supply component, and the drive component in the present invention.
- (37) FIG. **37** is a flow chart of judgment when the power management unit of the present invention is working.
- (38) FIG. **38** is a schematic diagram of modules of the battery assembly management device of the present invention.
- (39) FIG. **39** is a schematic flow chart of the battery pack management method of the present invention.
- (40) FIG. **40** is a schematic flowchart of step **S1**.
- (41) FIG. **41** is a schematic flowchart of step **S1** in another embodiment.
- (42) FIG. **42** is a schematic flowchart of step **S1** in another embodiment.
- (43) FIG. **43** is a schematic diagram of the structure of an electric vehicle.
- (44) FIG. **44** is a schematic diagram of the module of the charger of the present invention.
- (45) FIG. **45** is a schematic flowchart of an embodiment of a charger control method of the present invention.
- (46) FIG. **46** is a schematic diagram of the cooperation between a charger and a battery assembly according to an embodiment of the present invention.
- (47) FIG. **47** is a three-dimensional schematic diagram of the charger shown in FIG. **46**.
- (48) FIG. **48** is a flowchart of the charging control method of the present invention.
- (49) FIG. **49** is a schematic flowchart of an embodiment of a charger control method of the present invention.
- (50) FIG. **50** is a schematic flowchart of another embodiment of a charger control method of the present invention.
- (51) FIG. **51** is a flowchart of the charging control method of the present invention.
- (52) FIG. **52** is a schematic diagram of a three-dimensional structure of an electric tool.

DETAILED WAYS

- (53) The following describes the implementation of the present invention through specific examples, and those skilled in the art can easily understand other advantages and effects of the present invention from the content disclosed in this specification. The present invention can also be implemented or applied through other different specific embodiments, and various details in this specification can also be modified or changed based on different viewpoints and applications without departing from the spirit of the present invention.
- (54) It should be noted that the illustrations provided in this embodiment only illustrate the basic idea of the present invention in a schematic manner. The figures only show the components related to the present invention instead of the number, shape, and shape of the components in actual implementation. For the size drawing, the type, quantity, and proportion of each component can be changed at will during actual implementation, and the component layout type may also be more complicated.
- (55) As shown in FIGS. **1** to **3**, the present invention discloses a mount-type electric tool **100**, which includes a walking wheel **10**, a frame **20** mounted on the walking wheel **10**, and a frame **20** mounted on the frame **20** to perform the operation. The working mechanism (not shown) that functions of the mount-type electric power tool **100**, the driving mechanism **30** and the operating mechanism **40** that drive the traveling wheels **10** to work are described.
- (56) As shown in FIGS. **1** to **3**, the walking wheel **10** includes a front wheel **11** and a rear wheel **12** arranged opposite to the front wheel **11** and matched with the driving mechanism **30**. The front wheel **11** includes a front axle **111** and a first front wheel **112** and a second front wheel **113**

installed at both ends of the front axle **111**. The rear wheel **12** includes a first rear wheel **121** and a second rear wheel **122** opposite to the first rear wheel **121**.

(57) As shown in FIGS. **1** to **2**, the frame **20** is mounted on the walking wheel **10**, and includes a base **21** located between the front wheel **11** and the rear wheel **12** and the rear wheel **12** facing away from the front. The tail **22** on the side of the wheel **11**. The base **21** is provided with a pedal **211** and a seat **212**. The pedal **211** is located on the side of the base **21** away from the tail **22** for the user to step on. The seat **212** is located between the pedal **211** and the tail **22**. The tail portion **22** is provided with a receiving cavity **221** for receiving various tools, parts and the like. The operating mechanism is installed on the side of the base **21** facing away from the seat **212** to perform the functions of the mounted electric tool **100**. In this embodiment, the operating mechanism is a blade for mowing grass.

(58) As shown in FIG. **3**, the driving mechanism **30** is used to drive the rear wheel **12** to rotate, and includes a first motor **31** and a second motor **32** disposed opposite to the first motor **31**. The first motor **31** is provided with a first output shaft **311**. The first rear wheel **121** is mounted on the first output shaft **311** to be driven by the first motor **31** to rotate. The second motor **32** is provided with a second output shaft **321**. The second rear wheel **122** is mounted on the second output shaft **321** to be driven by the second motor **32** to rotate. The first output shaft **311** and the second output shaft **321** jointly constitute the output shaft of the driving mechanism **30** to output power to the traveling wheel **10**.

(59) As shown in FIG. **3**, the operating mechanism **40** includes a handle and a brake assembly matched with the handle; the brake assembly includes a brake disc mounted on the output shaft of the driving mechanism **30**, and is opposite to the brake disc. Matching brake calipers and brake cables; one end of the brake cable is connected to the handle, and the other end is connected to the brake caliper; when the handle is pushed to move from neutral to parking, the handle drives the brake cable Movement so that the brake caliper clamps the brake disc under the action of the brake wire.

(60) As shown in FIGS. **3** to **4**, the operating mechanism **40** further includes a first control element **43** and a second control element **44**; the handle includes a first handle **41** and a second handle disposed opposite to the first handle **41** **45**; The brake assembly includes a first brake assembly **42** matched with the first handle **41** and a second brake assembly **46** matched with the second handle **45**. The first handle **41** includes a swing arm **411** that is pivotally mounted on the base **21** and swings in the second direction BB (as shown in FIG. The swing arm **411** is a control arm **412** that swings along the first direction AA (as shown in FIG. **4**). A support arm **413** is fixedly installed at one end of the swing arm **411** close to the control arm **412**, and the support arm **413** is located on the side of the control arm **412** away from the parking gear. This arrangement can effectively prevent the support arm **413** from obstructing the movement of the control arm **412** from the neutral gear to the parking gear. In this embodiment, the support arm **413** is located on the side of the control arm **412** facing the seat **212**.

(61) As shown in FIGS. **4** to **5**, the supporting arm **413** is provided with a pair of brackets **4131** and a cable fixing plate **4132** installed on the pair of brackets **4131** and used for fixing the brake cable. The bracket **4131** is provided with a mounting hole **4133**. The cable fixing plate **4132** is pivotally mounted on the bracket **4131** so that the cable fixing plate **4132** can rotate. One end of the cable fixing plate **4132** is provided with a limiting portion **4134**, and the other end is provided with a limiting hole **4135** and a limiting pin (not shown) matched with the limiting hole **4135**. The cable fixing plate **4132** passes through the mounting hole **4133**, and the pair of brackets **4131** are located between the limiting portion **4134** and the limiting pin. One side of the cable fixing plate **4132** is further provided with a bayonet **4136** for holding the brake wire, and the bayonet **4136** is located between the limiting portion **4134** and the limiting hole **4135**. The spacing between the limiting portion **4134** and the limiting pin is slightly larger than the spacing between the pair of brackets **4131**, so that the cable fixing plate **4132** can slide in the connecting direction of the pair of brackets

4131, Thereby making the movement of the brake cable more reliable. The first brake assembly **42** includes a first brake disc **421** mounted on the first output shaft **311**, a first brake caliper **422** matched with the first brake disc **421**, a first brake cable **423**, and a cable adjustment Rod **426**. The first brake wire **423** includes a brake sleeve **4231** and a steel wire **4232** located in the brake sleeve **4231**. One end of the brake sleeve **4231** is installed on the first brake caliper **422**, and the other end is installed on the cable adjusting rod **426**; the cable adjusting rod **426** is clamped and fixed on the bayonet **4136** to fix the Mentioned first brake line **423**. One end of the steel wire **4232** is installed on the brake caliper **422**, and the other end is connected to the control arm **412**. The cable adjusting rod **426** is used to adjust the tightness between the brake sleeve **4231** and the steel wire **4232**, thereby adjusting the braking effect. The cable adjusting rod **426** is an existing structure. Since the cable adjusting rod **426** is mounted on the cable fixing plate **4132**, and the cable fixing plate **4132** can be rotated, the cable adjusting rod **426** can freely adjust the angle according to the position of the control arm **412**, and then This allows the user to easily pull the steel wire **4232**. A flange **424** is installed on the first output shaft **311**, and the first brake disc **421** is installed on the flange **424**. A first brake spring **425** is also provided between the first brake wire **423** and the first brake caliper **422**. The first control element **43** is used to cooperate with the control arm **412** and the second handle **45** of the first handle **41** to control the driving mechanism **30** to be energized or de-energized.

(62) As shown in FIGS. **4-6**, there are, for example, two first control elements **43**, which are matched with the first handle **41** and the second handle **45**, respectively. In this embodiment, the first control element **43** is a switch. However, it can be understood that the first control element **43** may also have other structures. For example, the first control element **43** may be a displacement sensor, and the displacement sensor controls the driving mechanism **30** to be energized or de-energized according to the displacement of the control arm **412**. The present invention does not limit the specific structure of the first control element **43**. The second control element **44** is used to cooperate with the swing arm **411** to control the driving mechanism **30** to rotate forward or reverse, or accelerate or decelerate. In this embodiment, the second control element **44** is a rotational position sensor. However, it can be understood that the second control element **44** may also have other structures, such as a pressure sensor, a distance sensor, and so on. The present invention does not limit the specific structure of the second control element **44**. The second brake assembly **46** includes a second brake disc **461** installed on the second output shaft **321**, a second brake caliper **462** matched with the second brake disc **461**, and a second brake wire **463**. One end of the second brake wire **463** is connected to the second handle **45**, and the other end is connected to the second brake caliper **462**. A flange **464** is installed on the second output shaft **321**, and the second brake caliper **462** is installed on the flange **464**. A second brake spring **465** is also provided between the second brake wire **463** and the second brake caliper **462**.

(63) As shown in FIGS. **4-6**, the second brake assembly **46** is controlled by the second handle **45**, but it is understandable that the first brake assembly **42** and the second brake assembly **46** can pass through at the same time. The first handle **41** is controlled, that is, one end of the second brake wire **463** is connected to the second brake caliper **462**, and the other end is connected to the control arm **412**.

(64) As shown in FIGS. **4-6**, the first output shaft **311** and the second output shaft **321** are further provided with a first keyway (not shown), and the flanges **424**, **464** are also provided with a first keyway. Oppositely arranged second key grooves (not shown), the first key grooves and the second key grooves are matched by a moment key to transmit the power output by the first output shaft **311** and the second output shaft **321** to the Flange **424**, flange **464**.

(65) As shown in FIG. **4**, when the first handle **41** is pushed in the first direction AA to move from neutral to parking, the control arm **412** drives the first brake wire **423** to move, so that the first the brake caliper **422** clamps the first brake disc **421** under the action of the first brake wire **423** to achieve parking brake. At this time, the control arm **412** cooperates with the first control element

43 to control the driving mechanism **30** is powered off. When the first handle **41** moves from the parking position to the neutral position, the first control element **43** controls the driving mechanism **30** to be powered on. When the first handle **41** is pushed in the second direction BB to move from the neutral position to the second position (that is, the forward position), the driving mechanism **30** rotates forward to drive the mounted electric tool **100** forward; When the first handle **41** is moved from the neutral position to the third position (that is, the reverse gear) in the two directions BB, the driving mechanism **30** reverses to drive the mounted electric tool **100** to move backward. When the second handle **45** is pushed in the first direction AA to move from neutral to the fourth position (that is, the brake gear), the second handle **45** drives the second brake wire **463** to move, so that the second the brake caliper **462** clamps the second brake disc **461** under the action of the second brake wire **463** to achieve parking brake. At this time, the second handle **45** cooperates with the first control element **43** to the driving mechanism **30** is controlled to be powered off. Due to the simple structure and high reliability of the first brake assembly **42** and the second brake assembly **46**, the cumbersome operation of manual release of the existing electromagnetic brake can be effectively avoided when the whole machine cannot be powered on. The user only needs to place the first handle **41** and the second handle **45** in the neutral position, and then can easily push the mount-type electric tool **100** to a maintenance point for maintenance.

(66) As shown in FIG. 1, the present invention also discloses a mounted lawn mower, including a walking wheel **10**, a frame **20** mounted on the walking wheel **10**, and a frame **20** mounted on the frame **20** to perform lawn mowing work. A cutter head assembly (not shown), a driving mechanism **30** and an operating mechanism **40** that drive the traveling wheel **10** to work.

(67) As shown in FIG. 1, the parking brake of the mount-type electric tool **100** of the present invention has a simple structure, high reliability, and low cost. When the power fails, the user can easily release the brake to push the mount-type electric tool **100** for maintenance. Point for repairs.

(68) As shown in FIGS. 7-8 and 12, the present invention discloses an electric tool **100**, which includes a frame **20**, a drive assembly **511** installed at the bottom of the frame **20**, a steering assembly **504**, and a brake assembly (not shown), a power supply unit **525**, a control unit **526**, and an operating mechanism **507**. The power supply component **525** supplies power to the driving component **511**, the control component **526** and the operating mechanism **507**. In this embodiment, the operating mechanism **507** is a cutter head assembly for cutting grass, but in other embodiments, the operating mechanism **507** may also be a snow shovel, a snow sweeping assembly, a blowing and suction assembly, and the like. The electric tool **100** may be an electric vehicle, for example, an electric lawn mower.

(69) As shown in FIGS. 7-9, the frame **20** includes a frame **501**, a shell **502** mounted on the frame **501**, a seat **212** mounted in the middle of the frame **501**, and a seat **212** mounted on the frame **501**. The suspension assembly **509**, the left foot control assembly **505**, and the right foot control assembly **506** at the front of the frame **501**. The frame **501** and the housing **502** jointly form a receiving cavity **221** for receiving the power supply assembly **525** and the control assembly **526**. The seat **212** is pivotally mounted on the frame **501** and located above the receiving cavity **221**. When the seat **212** is rotated, the receiving cavity **221** is exposed to the outside, so that the user can place or take out the power supply assembly **525** and the control assembly **526**. In this embodiment, the power supply assembly **525** is located directly below the seat **212**, and the control assembly **526** is located on the side of the power supply assembly **525** away from the operating mechanism **507**. The suspension assembly **509** includes a cantilever **508** pivotally mounted on the front end of the frame **501** and an elastic element (not shown) that cooperates with the cantilever **508**, and one end of the elastic element is fixedly mounted on the frame. On the frame **501**, the other end is fixedly installed on the cantilever **508**. The operating mechanism **507** is fixedly mounted on the cantilever **508** so that the operating mechanism **507** can rotate around the pivot through the cantilever **508**. The elastic element is used to assist the working mechanism **507** to lift up or to act as a buffer when the working mechanism **507** is lowered. For example, when the

operating mechanism **507** travels from flat to high ground, the elastic element assists the lifting of the operating mechanism **507**; when the operating mechanism **507** travels from high to flat ground, the elastic element assists the operating mechanism **507** dropped, playing a buffering role.

(70) As shown in FIGS. **10-11**, the left foot control assembly **505** includes a left foot pedal **522**, a gear **523** matched with the left foot pedal **522**, and a chain **524** matched with the gear **523**. The left foot pedal **522** is pivotally mounted on the frame **501** and can drive the gear **523** to rotate. One end of the chain **524** is fixedly installed on the frame **501**, the other end is fixedly installed on the operating mechanism **507**, and the middle part of the chain is wound on the gear **523**. When a user steps on the left foot pedal **522** and causes the left foot pedal **522** to rotate, the left foot pedal **522** drives the gear **523** to rotate. At this time, the gear **523** drives the chain **524** to move. In turn, the operating mechanism **507** is lifted upward under the action of the chain **524**. With this arrangement, the operating mechanism **507** can smoothly overcome obstacles. When the user releases the left foot pedal **522**, the operating mechanism **507** is reset under the action of gravity. The right foot control assembly **506** includes a right foot pedal pivotally mounted on the frame **501** and a walking sensor (not shown) matched with the right foot pedal. When the user steps on the right pedal to rotate the right pedal, the walking sensor senses information such as the forward rotation, reverse rotation, and rotation amplitude of the right pedal, and transmits the information to the control Component **526**. The control component **526** controls the driving component **511** to advance, retreat, or stop according to the foregoing information.

(71) As shown in FIGS. **7-8**, the driving assembly **511** includes a front drive assembly **512** installed at the bottom end of the front part of the frame **501** and a rear drive assembly **513** installed at the bottom end of the rear part of the frame **501**. One of the front drive assembly **512** and the rear drive assembly **513** is pivotally mounted on the frame **20** so that it can rotate around the frame **20**, and the other is fixedly mounted on the frame **20**. In this embodiment, the front drive assembly **512** is fixedly installed on the frame **20**; the rear drive assembly **513** is pivotally installed on the frame **20** so as to cooperate with the steering assembly **504** to achieve the power tool **100** turns. The front drive assembly **512** includes a pair of front drive wheels **11**, and the pair of front drive wheels **11** are fixedly installed on both sides of the frame **20**. The front driving wheel **11** includes a front wheel hub motor **31** and a front wheel **112** mounted on the front wheel hub motor **31**.

(72) As shown in FIGS. **13-14**, the rear drive assembly **513** includes a rear drive axle **517**, rear drive wheels **12** fixedly installed on both sides of the rear drive axle **517**, and pivotal connections installed on the rear drive axle **517**. Component **528**. The rear driving wheel **12** includes a rear hub motor **527** and a rear wheel **122** mounted on the rear hub motor **527**. The pivot assembly **528** includes a fixing frame **518**, a steering wheel **519** matched with the fixing frame **518**, a first pivot **520** arranged in a horizontal direction, and a second pivot **521** arranged in a vertical direction. The fixing frame **518** is fixedly installed at the rear end of the rack **20**. The steering wheel **519** is pivotally mounted on the fixing frame **518** by the second pivot shaft **521** in the vertical direction, and is pivotally mounted on the rear drive shaft by the first pivot shaft **520** in the horizontal direction. On the bridge **517**. Since the rear drive axle **517** is pivotally mounted on the frame **20** through the second pivot shaft **521**, the rear drive axle **517** can rotate around the second pivot shaft **521** in a horizontal plane, so that the electric tool **100** can turn. Since the rear drive axle **517** is pivotally mounted on the pivot assembly **528** through the first pivot **520**, the rear drive axle **517** can rotate about the first pivot **520** in a vertical plane. With this arrangement, when the electric tool **100** is walking on uneven grass, the rear drive axle **517** can freely rotate around the first pivot **520** as needed, so that the front drive wheel **11** and the rear drive wheel **12** can land on the ground at the same time, avoiding the problem of a wheel hanging in the air when the existing electric vehicle is walking on uneven roads. The frame **20** is also provided with a limiting member (not shown) that cooperates with the rear drive axle **517** to limit the rotation angle of the rear drive axle **517** in a vertical plane.

(73) As shown in FIGS. **8-9**, the steering assembly **504** includes a driving wire **514** and a steering

wheel **510** that drives the driving wire **514** to rotate. The two ends of the driving wire **514** are fixedly installed on both sides of the steering wheel **519** respectively. When the steering wheel **510** is rotated, the steering wheel **510** drives the drive wire **514** to rotate, thereby pulling the steering wheel **519** to rotate around the second pivot **521**, so that the rear drive axle **517** is positioned on the steering wheel. Under the action of the **519**, it rotates around the second pivot **521**, thereby realizing the steering of the electric vehicle **100**. Of course, it can be understood that, in other embodiments, the two ends of the drive line **514** can also be directly fixedly installed on the rear axle **517** and located on the two sides of the second pivot **521** respectively. The driving wire **514** is provided with a chain, and the steering wheel **510** is provided with a gear matched with the chain.

(74) As shown in FIG. **12**, the control assembly **526** is installed in the receiving cavity **221** and located at the rear of the frame **20**. The control component **526** is used to control the operation of the driving component **511**. The control component **526** may be a single-chip microcomputer, a central processing unit, etc., or a control circuit formed by a logic circuit, or a combination of the two. When the electric tool **100** moves forward, the control assembly **526** controls the front drive assembly **512** and the rear drive assembly **513** to drive the electric tool **100** to move forward. At this time, the front drive wheel **11** and the rear drive wheel **12** is configured such that the rotation speed of the front driving wheel **11** is not less than the rotation speed of the rear driving wheel **12**. With this arrangement, the power tool **100** can always be in a state in which the frame **20** is dragged forward by the rear drive axle **517** through the pivot assembly **528** during the forwarding process, thereby avoiding the rear drive axle. The rotation speed of the wheels **12** is greater than that of the front driving wheels **11**, which causes the rear drive axle **517** to hit the pivotal assembly **528**, thereby eliminating the collision sensation that occurs during the driving of the existing electric vehicle, and improving the stability of the whole machine. performance. When the electric tool **100** is in an acceleration process, the acceleration of the front driving wheel **11** is greater than the acceleration of the rear driving wheel **12**. Of course, it can also be set as follows: the acceleration time of the front drive wheel **11** is less than the acceleration time of the rear drive wheel **12**; the difference between the acceleration time of the rear drive wheel **12** and the acceleration time of the front drive wheel **11** is 0.2 Second. In addition, when the electric tool **100** is in an acceleration process, the front driving wheel **11** and the rear driving wheel **12** may also be set such that the acceleration of the front driving wheel **11** is not less than the acceleration of the rear driving wheel **12**, and the front driving wheel **11** starts to accelerate a preset time earlier than the rear driving wheel **12**. This arrangement can also avoid the problem that the rear drive axle **517** hits the pivot assembly **528** due to the rotation speed of the rear drive wheel **12** being greater than that of the front drive wheel **11**. When the electric tool **100** turns, the pair of rear drive wheels **12** of the rear drive assembly **513** are set such that the speed of the rear drive wheel **12** located inside the turning radius is less than the speed of the rear drive wheel **12** located outside the turning radius. Such a setting can avoid the tire wear problem caused by the same speed of the pair of rear driving wheels when the existing electric vehicle is turning. The difference between the rotational speed of the rear drive wheel **12** located inside the turning radius and the rotational speed of the rear drive wheel **12** located outside the turning radius is inversely proportional to the turning radius. Of course, it can be understood that, in other embodiments, the difference between the rotational speed of the rear drive wheel **12** located inside the turning radius and the rotational speed of the rear drive wheel **12** located outside the turning radius can also be set to be the same as that of the rear drive axle **517**. The angle of rotation in the horizontal plane is proportional.

(75) As shown in FIGS. **9** and **14**, when the electric tool **100** is in the deceleration process, the control assembly **526** controls the brake assembly to work, and makes the acceleration of the front drive wheel **11** greater than that of the rear drive wheel **12**. Acceleration, that is, the decreasing speed of the rotation speed of the front driving wheel **11** is less than the decreasing speed of the rotation speed of the rear driving wheel **12**. Of course, it is understandable that when the electric tool **100** is in the deceleration process, it can also be set to: the deceleration time of the front drive

wheel **11** is greater than the deceleration time of the rear drive wheel **12**, or the front drive wheel **11**. The acceleration of **11** is not less than the acceleration of the rear driving wheel **12**, and the rear driving wheel **12** starts to decelerate ahead of the front driving wheel **11** by a preset time. In this embodiment, the control component **526** controls the operation of the brake component, but in other embodiments, the brake component can also be directly controlled by the user. When the user controls the brake assembly to brake, the brake assembly brakes the rear drive wheel **12**, and the control assembly **526** controls the power supply assembly **525** to power off the front drive assembly **512**.

(76) As shown in FIG. **9**, the electric tool **100** of the present invention directly drives the wheels to rotate through the hub motor, so that the transmission gear box can be omitted, thereby avoiding the problem that the existing gear box drive structure requires regular maintenance and oil replacement, saving labor costs and reducing In addition, since the speed of the front drive wheel **11** is not less than the speed of the rear drive wheel **12**, the front drive assembly **512** and the rear drive assembly **513** will not collide with the frame **20**, thereby eliminating the driving process. The rotation speed of the rear driving wheel **12** is greater than the rotation speed of the front driving wheel **11**, which causes the collision problem, so that the whole machine travels more smoothly.

(77) The invention also discloses a control method for an electric vehicle, which includes the following steps: **S1**: Detect the movement state of the electric tool **100**; when the electric tool **100** is accelerating, skip to step **S2**; otherwise, skip to step **S3**; **S2**: Control the acceleration of the front drive assembly **512** and the rear drive assembly **513** so that the rotation speed of the front drive wheel **11** is greater than the rotation speed of the rear drive wheel **12**; **S3**: Control the deceleration of the front drive assembly **512** and the rear drive assembly **513** so that the rotation speed of the front drive wheel **11** is greater than the rotation speed of the rear drive wheel **12**.

(78) The step **S2** further includes: controlling the front-wheel drive assembly **512** to start accelerating in advance of a preset time than the rear-drive assembly **513**.

(79) The step **S3** further includes: controlling the front drive assembly **512** to start decelerating after a preset time delay from the rear drive assembly **513**. Alternatively, the front drive assembly **512** is directly controlled to power off, and the rear drive assembly **513** is controlled to brake.

(80) As shown in FIGS. **15-16**, the present invention also provides an electric tool **100**, which includes a frame **20**, a seat assembly **212** respectively disposed on the frame **20**, an electric unit **529**, a manipulation unit **40**, and a battery management system **537**. The battery management system **537** may also be defined as a battery system.

(81) As shown in FIG. **15**, the frame **20** is used to carry the seat assembly **212** for the operator to ride; the frame **20** extends along the running direction of the power tool **100**, and the seat assembly **212** is located at the center line of the frame **20** perpendicular to its running direction. One side. The frame **20** is provided with a cover assembly **530** for protecting the power consumption unit **529**, the manipulation unit **40**, and the battery management system **537**, and the cover assembly **530** is arranged around the seat assembly **212**.

(82) As shown in FIGS. **15-17**, the power consumption unit **529** includes a working component **531** detachably connected to the frame **20** and a walking component **532** for driving the electric tool **100** to walk, that is, the working component **531** can be defined as the first power consumption unit, the walking component **532** can also be defined as the second power-consuming unit. Of course, the power consumption unit **529** may also include a third power consumption unit and a fourth power consumption unit. The working assembly **531** is electrically connected with the operating unit **40** to complete the corresponding gardening tasks under the control of the operating unit **40**. The working assembly **531** has a working member **540** (i.e., a cutter) for realizing gardening work and a working member for carrying the work. The components of **540** are welded **541**, and the working component **540** is detachably connected to the frame **20** through the component welding **541**. With this arrangement, on the one hand, it is convenient to disassemble and replace the working components **531**, so that the same electric tool **100** can complete a variety

of gardening tasks, which effectively improves the use range of the electric tool **100**; on the other hand, when the power of the electric tool **100** is too low. The working assembly **531** can be directly removed to reduce the self-weight of the electric tool **100**, so that it can return to the charging/storage position with the electric power, and perform charging/maintenance to ensure the convenience of using the electric tool **100**.

(83) As shown in FIG. **17**, multiple working members **540** may be provided at the same time to improve the working efficiency of the electric tool **100**. The working assembly **531** also includes a driving member **533** for driving the working member **540** to operate. The driving member **533** and the working member **540** are arranged in a one-to-one correspondence, and the driving member **533** is, for example, a driving motor. Of course, the same driving member **533** can also drive multiple Working member **540**.

(84) As shown in FIGS. **15-17**, the working component **531** is, for example, a mowing component, and the working component **540** is a mowing component used to perform mowing operations. The number of working components **540** corresponds to the number of driving components **533** to ensure cutting. The working efficiency of the grass component **131** when mowing the grass.

(85) As shown in FIGS. **15-17**, the work component **531** can also be a garden work component used to perform other garden work tasks, such as a snowplow. It is only necessary to ensure that the work component **531** can be adapted to the frame **20** and can be manipulated by the unit. **40**.

Manipulation control is sufficient. That is, in the drawings and specification of the present invention, only the electric tool **100** is a riding lawn mower and the working assembly **531** is a lawn mower as an example for illustration, but it should not be used as an example. limit.

(86) As shown in FIGS. **15-16**, the walking assembly **532** is used to drive the electric tool **100** to travel, and the walking assembly **532** includes a front wheel assembly **11** and a driving wheel assembly **12**. Wherein, the front wheel assembly **11** includes a rotating wheel **113** rotatably connected to the front end of the frame **20** and a steering mechanism (not shown) for controlling the turning of the rotating wheel **113**, and the rotating wheel **113** is a universal wheel, and the rotating wheel **113** is a smooth surface. The steering wheel can effectively avoid the influence of the rotating wheel **113** on the working ground when it rotates.

(87) As shown in FIG. **18**, the driving wheel assembly **12** is used to drive the electric tool **100** to run and realize steering, and includes two sets of driving wheels **122**, a reduction box **542**, and a driving motor **543**. Among them, the two driving wheels **122** are respectively arranged at the end of the frame **20**. On both sides of the end, the reduction gear box and the driving motor jointly constitute a driving axle for controlling the operation of the driving wheels **122**, and the driving axle and the driving wheels **122** are arranged correspondingly.

(88) As shown in FIG. **15**, the drive axle is installed under the frame **20**, and the drive axle can control the two drive wheels **122** to perform differential motions respectively, which can effectively increase the steering angle of the drive wheels **122** and make the drive wheel assembly **12** The zero steering mechanism with the turning radius infinitely approaching zero further improves the practicability and usability of the electric tool **100**.

(89) As shown in FIG. **15**, the manipulation unit **40** is arranged on the frame **20**, and is used to control the operation of the power consumption unit **529** in the electric tool **100**; in the present invention, the manipulation unit **40** includes an electric control unit **534** and an electric control unit **534**. A control panel **535** that is sexually connected and a height adjustment unit **536** for adjusting the operating height of the electric tool **100**.

(90) As shown in FIG. **15**, the electrical control unit **534** is used to collect the operating signals transmitted by the electrical unit **529**, the battery management system **537**, and the control panel **535**, judge the operating signals, and issue corresponding instructions to control the electrical unit **529**/battery The management system **537**/control panel **535** executes corresponding actions or performs corresponding displays.

(91) As shown in FIG. **15**, the control panel **535** is used to receive instructions from the operator,

and send corresponding operating signals to the electrical control unit **534** for processing, so as to further complete the corresponding garden work or function switching according to the operator's requirements to achieve The purpose of improving the convenience of use of the electric tool **100**. (92) As shown in FIG. **15**, the height adjustment assembly **536** includes an adjustment structure (not shown) for adjusting the relative height between the rack **20** and the working ground under the frame **20**, and an adjustment member (not labeled) for controlling the adjustment structure. The high component **536** is located on the side of the seat assembly **212** to facilitate the use of the operator and improve the convenience of use of the electric tool **100**. Of course, the height adjustment assembly **536** can also be located at the foot pedal position at the front end of the frame **20**. At this time, the adjustment structure can be controlled by stepping on the pedal adjustment member, which further improves the convenience of use of the electric tool **100**.

(93) As shown in FIGS. **19** and **21**, the battery management system **537** is installed on the frame **20** to provide power to the power tool **100**. In the present invention, the battery management system **537** includes a battery accommodating part **544** and a control component **549**.

(94) As shown in FIGS. **19-20**, the battery accommodating part **544** is fixedly arranged on the rack **20** for accommodating a plurality of battery packs **539**, and the battery pack **539** is detachably connected to the battery accommodating part **544** to further make the battery pack **539** and The electric tool **100** can be detachably connected to facilitate the replacement of the battery pack **539**, and each battery pack **539** can supply power for at least one hand-held tool.

(95) As shown in FIG. **19**, the multiple battery packs **539** are divided into different power supply units **538** to supply power to the working component **531** and the walking component **532**, respectively. For example, FIG. **19** shows four power supply units **538**, such as a first power supply unit, a second power supply unit, a third power supply unit, and a fourth power supply unit from top to bottom. The first power supply unit, for example, supplies power for the first power consumption unit, the second power supply unit, for example, supplies power for the second power consumption unit, the third power consumption unit, for example, supplies power for the third power consumption unit, and the fourth power consumption unit, for example, the fourth power consumption unit. The electric unit supplies power, that is, different power supply units supply power to different electric units. The power supply unit **538** is composed of at least two battery packs **539** in parallel. The battery packs **539** in the same power supply unit **538** have the same rated voltage. This setting can facilitate the power supply unit **538** to achieve stable voltage output; the number of battery packs **539** in each power supply unit **538** is equal, so that each power supply unit **538** can Under the control of the control component **549** and the control unit **40**, the same power-consuming unit **529** is supplied with power to ensure the endurance of the power-consuming unit **529**. Each group of power supply units **538** has two battery packs **539** arranged side by side, and multiple groups of power supply The unit **538** is connected as a whole through an integral battery receiving portion **544**, so that a plurality of battery packs **539** are arranged in a matrix, and the battery packs **539** are arranged in a matrix to be connected and installed in the frame **20** and located under the seat assembly **212**. Of course, the battery management systems **537** arranged in a matrix can also be located at other positions of the rack **20**, such as the rear of the rack **20**, etc. That is, the specific location of the battery management system **537** can be selected according to the actual situation. To limit.

(96) As shown in FIG. **19**, the different power supply units **538** are arranged separately, that is, the battery accommodating portion **544** is arranged separately. In this way, the power supply unit **538** in the battery management system **537** or the battery pack **539** in the power supply unit **538** can be separated from each other. The power supply unit **538** or the battery pack **539** can be respectively arranged at different positions of the rack **20**. On the one hand, the distributed installation of the power supply unit **538**/battery pack **539** in the battery management system **537** is realized; on the other hand, it is convenient for the battery management system **537** to be the power consumption unit **529** supplies power.

(97) As shown in FIG. 19, when the power supply units 538 are installed in a distributed manner, multiple groups of power supply units 538 need to be evenly arranged on the frame 20, and the center of all battery packs 539 is located at the rotation axis of the drive wheel assembly 12 and the front wheel assembly 11 rotates. Between the axis. The weight at the upper position of the frame 20 is evenly distributed to ensure the smooth operation of the electric tool 100, and to prevent the shortening of the service life of the electric tool 100 caused by the excessive partial load of the frame 20 caused by uneven weight distribution.

(98) As shown in FIG. 19, the number of battery packs 539 in each power supply unit 538 may also be different. In this case, multiple power supply units 538 may simultaneously/respectively supply electric energy to power consumption units 529 with different rated powers. Specifically, when the number of battery packs 539 in each power supply unit 538 is different, for example, there is only one battery pack 539 in some power supply units 538, the power supply unit 538 can supply power to a working component 540 in the working assembly 531. It can be seen from FIG. 17 that there are three working members 540. In this embodiment, at least three power supply units 538 supply power to the three working members 540 respectively. At this time, the battery management system 537 also includes at least walking Another power supply unit 538 powered by the component 13, and the power supply unit 538 may have two battery packs 539.

(99) As shown in FIGS. 19-20, the power supply unit 538 also has a current adjustment component (not shown), which is electrically connected to the control component 549, and can adjust the power supply unit 538 under the control of the control component 549 The current is output so that the power supply units 538 with different numbers of battery packs 539 have the same power output, so that different power supply units 538 can be applied to the same power consumption unit 529 to ensure the normal operation of the power consumption unit 529.

(100) As shown in FIG. 19-20, the limitation on the number of battery packs 539 in the power supply unit 538 is only exemplary. In actual use, the number and arrangement of the battery packs 539 in each power supply unit 538 can be made according to actual needs. Choice should not be limited by this.

(101) As shown in FIGS. 19-20, each battery pack 539 in the present invention can be separated from the power tool 100 to supply power to the electrical components that are different from the electrical unit 529. In the present invention, the electrical components are A hand-held garden tool driven by the battery pack 539, and when the battery pack 539 in one group of power supply units 538 is disassembled for use, the other group or groups of power supply units 538 can still be the power-consuming units 529 electrically connected to it. Power supply ensures the normal use of the power tool 100. At the same time, the power supply battery pack applied to hand-held garden tools (as shown in FIG. 20) can also be used in the power supply unit 538 of the present invention after being disassembled, and only the rated power supply battery pack needs to be guaranteed. The voltage is equal to the rated voltage of the battery pack 539, and the discharge interface of the power supply battery pack and the connection structure of the battery pack match each other. This arrangement effectively improves the practicability of the electric tool 100 and reduces the use cost of the electric tool 100.

(102) As shown in FIGS. 21-22, the control component 549 is used to control each power supply unit 538 to individually complete the energy supply to the power consumption unit 529. The battery management system 537 also includes a charging management component 550 and discharging that are electrically connected to the control component 549, respectively. Management component 550a.

(103) As shown in FIGS. 21-22, the control component 549 is electrically connected to the operating unit 40. On the one hand, it is used to receive the communication signal transmitted by the operating unit 40 or the charging device and the discharging device and control the charging management component 550 or discharge management according to the communication signal. The work of the component 550a; on the other hand, it can also be used to receive the collection signal

transmitted by the charge management component 550 and the discharge management component 550a, and send a control signal according to the collection signal to control the charging management component 550 to charge or the discharge management component 550a to discharge. (104) As shown in FIGS. 21-22, the charging management component 550 includes an information collection module and a charging interface respectively corresponding to each power supply unit 538, wherein the information collection module is used to collect the power information and current information of each power supply unit 538. Voltage information, cell temperature information, and power information, and transmit them to the control component 549 for processing; the charging interface is used to realize the electrical connection between the power supply unit 538 and the charging device, so as to finally realize the charging of the power supply unit 538. Each charging interface has a shut-off member (not shown) electrically connected to the control assembly 549.

(105) As shown in FIGS. 21-22, the shutdown component can receive the control instruction sent by the control component 549 after the control component 549 receives the collected information collected by the information collection module, and act according to the control instruction of the control component 549. If the information collection module transmits the collected information such as voltage, current, and cell temperature to the control component 549, the control component 549 determines whether the relevant data exceeds the set control threshold. If it exceeds the control threshold, the control component 549 will Send out the corresponding signal to control the shut-off component to disconnect.

(106) As shown in FIGS. 21-22, the control component 549 can also be used to preset the charging threshold. When the control component 549 detects that the power information of any power supply unit 538/battery pack 539 collected by the information collection module is lower than the charging threshold and has not When the charging device is connected, the control component 549 sends a warning signal that the battery is too low to the operating unit 40, and displays it through the control panel 535, prompting the operator to charge; further, when the control component 549 receives the communication that is connected to the charging device When the signal is signaled, the control component 549 completes the charging of each power supply unit 538 through the charging interface in the order of the power supply unit 538's power from low to high, and only when the power supply unit 538 is in the charging state, the corresponding shut-off device is in the on state In order to prevent abnormal discharge of the power supply unit 538 to be charged, the charging efficiency of the battery management system 537 is further improved.

(107) As shown in FIGS. 21-22, the electric tool 100 is provided with a charging interface, through which the charging device can charge all or part of the battery pack 539; of course, in other embodiments of the present invention, the battery pack 539 can also be used. It is disassembled from the power tool 100 and charged separately using a charger.

(108) As shown in FIGS. 21-22, in the process of charging the battery pack 539 alone, the charging sequence of the battery pack 539 is not particularly limited, and when multiple battery packs 539 are installed on the electric tool 100 for charging, the control assembly 549 detects the power of the battery pack 539. The charging can be carried out in the order of high to low, or in the order of low to high, or starting from the battery pack 539 with the middle power, or according to different the frequency of use of the power supply unit 538 determines the charging sequence.

(109) As shown in FIGS. 21-22, the discharge management component 550a includes a battery detection unit and a discharge interface corresponding to each power supply unit 538, wherein the battery detection unit is used to detect the number and output of the battery pack 539 in the corresponding power supply unit 538 Power and information such as the voltage, current and cell temperature of each battery pack 539 are transmitted to the control component 549 for processing, so as to supply power in the working state according to the number and/or output power of the battery pack 539 in each power supply unit 538 The switching of the unit 538, further, the battery detection unit is also set to balance the voltage of each battery pack 539 in the same power supply

unit **538**, and the battery detection unit can also be used to receive a control signal from the control component **549** to turn off the parallel Switch the power supply unit **538** in the power output state. (110) As shown in FIGS. **21-22**, the discharge interface is used to connect the power-consuming unit **529** and the operating unit **40** to provide power to it and ensure its normal operation. Further, the discharge management component **550a** further includes an external power conversion module **552** for achieving electric energy output. The external power conversion module **552** includes one or more of a USB interface, a lighting device interface, or a DC output device interface. The battery management system **537** and the power tool **100** of the present invention can also provide power for small electrical equipment such as lighting equipment, effectively improving the scope of application.

(111) As shown in FIGS. **21-22**, the control component **549** can also be used to preset the discharge threshold. In the present invention, the discharge threshold includes the threshold of the number of battery packs **539** in the power supply unit **538** and the current threshold of each power supply unit **538**/battery pack **539**. Voltage threshold/Temperature threshold/Power threshold; when the information collected by the discharge management component **550a** is the number of battery packs **539** in the power supply unit **538**, the control component **549** checks the number and quantity threshold of the battery packs **539** in each power supply unit **538**. Compare, and when the number of battery packs **539** in the power supply unit **538** in the working state is less than the preset number threshold, the control component **549** controls the power supply unit **538** to stop the output of power, and matches the power supply unit **538** in the idle state. The power-consuming unit **529** that needs electricity is provided to ensure the continuity of use of the power-consuming unit **529**. Incidentally, in the present embodiment, only the information management component **550a** discharge amount of information collected is illustrated as an example, when the information management component **550.sub.a** discharge acquired when other information, information such as current, voltage information, In the case of temperature information or power information, the control component **549** and the discharge management component **550a** can still switch the power supply unit **538** for energy output according to the above process.

(112) As shown in FIGS. **21-22**, the control component **549** also includes a battery protection component **551** electrically connected to the control component **549** and the power supply unit **538**, including battery pack overcurrent and overvoltage protection components, battery pack high and low temperature protection components, and battery protection components. The short-circuit protection component and the low-voltage protection component of the battery pack are used to monitor the battery pack **539** in the power supply unit **538** from time to time. When the battery pack **539** is abnormal in use, the battery protection component **153** can turn off the power supply unit **538** in time and stop the power supply unit **538**. The electric energy is sent out, and prompt information is sent to the control panel **535** through the control component **549**.

(113) As shown in FIGS. **18-19** and FIG. **21**, the battery management system **537** has 4 groups of power supply units **538**, each group of power supply units **538** has 2 battery packs **539**, and the 4 groups of power supply units **538** are connected in the same battery accommodating part **544** And the battery accommodating part **544** can be installed under the seat assembly **212**.

(114) As shown in FIG. **19**, the power supply unit **538** is used to supply power to the driving wheel assembly **12** and the external power conversion module **552** in the walking assembly **532** to ensure that the electric tool **100** is driven by the walking assembly **532** to walk in the work area.

(115) As shown in FIG. **19**, the power supply units **538** are used to supply power to the working components **531**, and the battery packs in each group of power supply units **538** can be used to supply power to the power supply units **538** individually. Or when more than one battery pack **539** is taken out, the working assembly **531** can still work normally.

(116) As shown in FIG. **16**, the electric tool **100** in the present invention is only exemplary. Of course, the battery management system **537** can also be used as a power source in golf carts, ATVs, electric bicycles, electric motorcycles, and unmanned lawn vehicles. Wait for electric power tools

driven by electricity.

(117) The terms “manipulation unit”, “control component”, “power consumption unit”, “battery management system” and the like in the present invention may include or relate to at least one of hardware and software.

(118) As shown in FIG. 16, the electric tool **100** of the present invention is powered by a battery management system **537**, and is provided with multiple sets of power supply units **538** and a control component **549** for controlling the power supply unit **538**, so that the control component **549** can control the power supply unit **538** to be different. The power consumption unit **529** independently supplies power, which avoids the abnormal use of the power tool **100** and the battery management system **537** caused by the damage of the battery pack **539** in the single power supply unit **538**, making the lawn mower using the battery management system **537** easy to use, Has a high use efficiency and a good user experience.

(119) As shown in FIGS. 23-24, the present invention provides an energy management system **562** for adjusting the use state of the electric tool **100**.

(120) As shown in FIG. 23, there are at least two sets of electric tools **100** connected to the energy management system **562**, and each set of electric tools **100** includes a working component **531** for performing a corresponding work task, and a drive for driving the working component **531** to work. The assembly **560** and the battery assembly **555** for powering the driving assembly **560**. The working component **531** and the driving component **560** can also be defined as power consumption units, that is, the energy management system **562** can be electrically connected to the working component **531** and the driving component **560**.

(121) As shown in FIG. 23, the energy management system **562** includes an energy control unit **556** and an energy management unit **559**. The energy control unit **556** is electrically connected to the electric tool **100** and the energy management unit **559**, respectively, and includes a collection device **557** and a control device **558** for receiving control instructions issued by the energy management unit **559** and controlling the state adjustment of the electric tool **100**. Further, the control device **558** is electrically connected to the driving assembly **560** to control the output speed of the driving assembly **560**.

(122) As shown in FIG. 23, the collecting device **557** is electrically connected to the driving assembly **560**, the battery assembly **555**, and the energy management unit **559** in each electric tool **100**, so as to collect information about the use status of the electric tool **100**, that is, collecting work Use status information of the component **531**, the driving component **560**, and the battery component **555**.

(123) As shown in FIG. 23, the usage status information collected by the collection device **557** includes at least the voltage information, current information, rotational speed information and output power information of the battery assembly **555** in each electric tool **100**. It should be noted that the types of use status information exemplified in the invention are only exemplary, and are not limited thereto.

(124) As shown in FIG. 23, the collection device **557** can simultaneously collect the power information, current information, and drive component **560** information of the battery assembly **555**, or different collection devices **557** can separately collect the power information of the battery assembly **555** and the rotational speed information of the drive component **560**.

(125) As shown in FIG. 23, the control device **558** is electrically connected to the energy management unit **559** and the drive assembly **560** and/or the battery assembly **555**. Specifically, the control device **558** is used to receive the control instructions issued by the energy management unit **559** and perform the control command adjusts the rotation speed of the driving assembly **560** and/or the output of the battery assembly **555**, and further adjusts the use state of the electric tool **100** to ensure that the energy of each electric tool **100** is in a balanced state.

(126) As shown in FIGS. 23-24, the energy management unit **559** is configured to collect the usage status information transmitted by each energy control unit **556**, and calculate the status between

different power usage units (for example, the working components **531**) based on the usage status information. Difference. In the present invention, the state difference value is the absolute value of the difference value of the state information used in different power-consuming units, and the types of state information used for calculating the state difference value are the same to ensure the accuracy of the calculation result. The use state information selected by the present invention for calculating the state difference is the remaining power information of the battery assembly **555** in different electric tools **100**, that is, at this time, the state difference is the power difference C. This setting can facilitate the energy management unit **559** evaluates the output power and/or power consumption of the electric tool **100** to further facilitate the evaluation of the use state of the electric tool **100**.

(127) As shown in FIGS. **23-24**, the energy management unit **559** is also configured to set a control threshold M. Specifically, when the energy management unit **559** detects that any state difference value acquired by the collection exceeds the corresponding control threshold M, the energy management unit **559** issues control instructions to the energy control unit **556**, and the use state of the electric tool **100** is adjusted through the energy control unit **556**.

(128) As shown in FIGS. **23-24**, the energy management unit **559** is configured to summarize the usage status information from each energy control unit **556** and calculate the status difference. Specifically, the energy management unit **559** can be used to set a control threshold. M. Input control instructions and send control instructions to the energy control unit **556**, and the interactive device can also be used to display the use status information of each electric tool **100** to facilitate the operator to control and manage the power tool **100** in real time according to the use status information.

(129) As shown in FIGS. **23-24**, the setting of the control threshold M in the present invention can be either the fixed information preset by the energy management system **562** at the factory, or the setting made by the operator according to actual needs during use. Adjustable information.

(130) As shown in FIGS. **23-24**, the control command is control information used to adjust/control the working state of the electric tool **100**, which can be a current control command, a voltage control command, etc., used to adjust the working state command or speed of the battery assembly **555**. A control command or the like is used to adjust any one of the working state commands of the driving component **560**, and the control command is a power control command used to control the output power of the driving component **560**.

(131) As shown in FIG. **25**, the present invention also provides an energy management method that uses the energy management system **562** to perform energy management and control on the electric tool **100**. The energy management method includes the following steps: S1. The energy control unit **556** collects and obtains the usage status information of each electric tool **100**, and transmits it to the energy management unit **559** for processing; S2. The energy management unit **559** calculates and obtains the state difference between the different electric tools **100** according to the use state information; S3. The energy management unit **559** compares the state difference with the preset control threshold M, and sends a control instruction to the energy control unit **556** according to the comparison result to adjust the working state of the electric tool **100**.

(132) The steps S1 to S3 will be described in detail below in conjunction with the specific structure of the energy management system **562**.

(133) Step S1 can be:

(134) S11. The energy control unit **556** collects within a set time or real-time collection and acquisition of the usage status information of each electric tool **100** connected to the energy control unit **556**; S12. The energy management unit **559** receives the usage status information of each electric tool **100**, and performs summary statistics on the usage status information of each electric tool **100**.

(135) In step S11, the set time is specifically collected by the collecting device **557** to obtain the usage status information of each electric tool **100** at the same time point and within the same time

interval. The accuracy of the energy evaluation is to avoid the difference in energy consumption of each electric tool **100** due to different collection times, which will then affect the energy evaluation result of the energy management system **562**.

(136) In step **S12**, the energy management unit **559** may classify the usage status information according to the category of the usage status information collected by the collection device **557**, so as to avoid confusing the summary statistics of the usage status information, which will affect subsequent calculations.

(137) Step **S2** is specifically that the energy management unit **559** calculates and obtains the state difference between different electric tools **100** according to the use state information. In the present invention, each use state information corresponds to at least one state difference value, that is, the state in the present invention. The type of the difference is consistent with the type of the collected usage status information, the status difference is the power difference **C**, and the usage status information is the remaining power information of the battery assembly **555**.

(138) As shown in FIG. **26**, step **S3** can be: **S31**. The energy management unit **559** compares the calculated state difference values in the initial use state, and selects the first state difference value **N**; **S32**. The energy management unit **559** compares the first state difference **N** with the control threshold value **M**. When $N > M$, the energy management unit **559** issues a control instruction to the energy control unit **556** to adjust the use state of the electric tool **100** from the initial use state to adjust the state of use; **S33**. The energy control unit **556** continuously collects the use state information of the electric tool **100** in the adjusted use state, and the energy management unit **559** summarizes the use state information in the adjusted use state, and calculates the second state difference value **N** in the selected adjusted use state; **S34**. The energy management unit **559** compares the second state difference **N'** with the control threshold **M**. When $N' < M$, the energy management unit **559** issues a control instruction to the energy control unit **556** to adjust the use state of the electric tool **100** Self-adjust the use state to the initial use state.

(139) As shown in FIG. **26**, the initial use state is the rated use state of the electric tool **100**, that is, when the electric tool **100** is in the initial use state, the battery assembly **555** is fully charged and the drive assembly **560** works according to the rated power, and the adjusted use state is the electric tool **100**. When the power of the middle battery component **555** is insufficient/lower than the average power level, the driving component **560** operates at a power lower than the rated power.

(140) As shown in FIG. **26**, in step **S31**, the first state difference value **N** is the state difference value with the largest value among the state difference values in the initial use state.

(141) As shown in FIG. **26**, in step **S32**, the energy management unit **559** compares the first state difference value **N** with the control threshold value **M**. When $N > M$, the energy management unit **559** identifies the value used to calculate the first state difference value **N**. Two electric tools **100**, and mark the electric tools **100** with low usage status information (such as low remaining power/low output current) among the two electric tools **100**, and further mark the electric tools **100** with the energy control unit **556**. The use state of the tool **100** is adjusted to reduce the rotation speed of the drive assembly **560** or the output voltage of the battery assembly **555** without affecting the use effect of the working assembly **531**, and reduce the power of the drive assembly **560**, so that the use state of the electric tool **100** is free. From the initial use state to the adjusted use state, the energy between the marked power tool **100** and the remaining power tools **100** is further balanced.

(142) As shown in FIG. **26**, in step **S33**, the second state difference value **N'** is the state difference value of the largest value among the state difference values in the adjusted use state.

(143) As shown in FIG. **26**, the energy management unit **559** compares the second state difference value **N'** with the control threshold value **M**. When $N' < M$, the energy management unit **559** identifies the power tool **100** that is operating in the adjusted state of use. **100**, and issue a control command through the energy control unit **556** to control all the drive components **560** connected to the energy management system **562** to have the same rotation speed or the battery components **555**

to have the same output power, and the electric tool **100** will self-adjust and return to the initial use state. Or work according to the maximum power.

(144) As shown in FIG. **26**, the second state difference value **N'** is the state difference value of the largest value among the state difference values in the adjusted use state.

(145) As shown in FIGS. **27-28**, the present invention also provides an electric tool **100**. The electric tool **100** includes a frame **20**, a working system **561** and a power system (not labeled) provided on the frame **20**, and an energy management system **562** for adjusting the working state of the working system **561**.

(146) As shown in FIG. **27**, the frame **20** is used to carry the working system **561** and the power system. The working system **561** is detachably connected to the frame **20** and electrically connected to the energy management system **562**, including a component welding **541** detachably connected to the frame **20** and a component welding **541** arranged on the component welding **541** for realizing garden work tasks Power tools **100**.

(147) As shown in FIGS. **29-31**, the electric tool **100** is a lawn mower, and the electric tool **100** is a mowing work device. The working assembly **531** is a cutting knife for performing mowing tasks, and the two ends of the cutting knife **531a** have The wind blade **563** tilted upward in the vertical direction and the knife tip **565** located below the wind blade **563** for breaking the grass, the driving assembly **560** is a driving motor for driving the working assembly **531**, and the driving motor **560** and the cutting knife **531a** are arranged in a one-to-one correspondence to individually drive each cutting knife **531a** to operate. In this embodiment, the electric tool **100** is provided with 3 groups at the same time, and the 3 cutting knives **531a** are arranged on the component welding **530** by displacing the 3 drives. The motor **560** is drivingly connected to the component welding **530** to increase the mowing area of the mowing power tool **100**.

(148) As shown in FIG. **32**, the battery assembly **555** and the driving motor **560** are arranged correspondingly to supply power to each driving motor **560**, and each battery assembly **555** includes one or more battery packs **539**. In this embodiment, it is used for The battery assemblies **555** powered by the driving motor **560** are arranged in a matrix to form a whole to facilitate the installation of the battery assemblies **555**.

(149) As shown in FIG. **32**, the power system includes a walking assembly **12** for driving the electric tool **100** to walk and a battery unit **554** for powering the walking assembly. In the present invention, the electric tool **100** may be a riding garden tool, and the walking assembly **12** includes the front wheel assembly (not numbered) and the driving wheel assembly (not numbered) for driving the power tool **100** to travel, the battery unit **554** is electrically connected to the driving wheel assembly to provide power to the driving wheel assembly.

(150) As shown in FIG. **32**, the battery unit **554** includes one or more battery packs **539**, and in this embodiment, the battery unit **554** and the battery assembly **555** are both connected and installed in the battery mounting cavity **553** provided on the rack **20** to All the battery packs **539** in the electric tool **100** are arranged in a regular manner, so as to reduce the difficulty of designing and manufacturing the electric tool **100**.

(151) As shown in FIG. **33**, the energy management system **562** used to adjust the working state of the working system **561** is the aforementioned energy management system, which also has an energy control unit that is electrically connected to the electric tool **100** for collecting the usage state information of the electric tool **100** **556** and the energy management unit **559** for adjusting the working status of the electric tool **100** according to the usage status information collected by the energy control unit **556**, and the energy management system **562** can be used to execute the aforementioned energy management method, because the energy management in this embodiment The structure and function of the system **562** and the aforementioned energy management system are basically the same, so the same content will not be repeated in the following description.

(152) As shown in FIGS. **31-33**, during the use of the power tool **100** of this embodiment, the cutting blade **531a** is driven by the drive assembly **560** to run at a high speed, and the blade **565** is

used to break the grass. During the working process, the blade **563** A working space is formed between the panels welded to the component **541**, and the cutting blade **531a** generates negative pressure around the wind blade **563** during high-speed rotation, so as to absorb the grass broken by the blade tip **565** to the vicinity of the cutting blade **531a**, and The airflow is generated along the rotation direction of the three cutting blades **531a** to blow the broken grass out of the component welding **541** to complete the mowing work. However, due to the inconsistency of the amount of broken grass of the three cutting blades **531a** during the mowing process, the three cutting blades **531a** the load is inconsistent, which further leads to inconsistency with the actual power used by the three drive components **560**.

(153) As shown in FIGS. **31-33**, the remaining power of the battery assembly **555** in each electric tool **100** will differ greatly after the electric tool **100** is used for a period of time. The energy management system **562**, which is electrically connected to the component **555**, begins to evaluate the power of the battery component **555** in the three groups of power tools **100**. Under the condition of ensuring the mowing effect of the power tool **100**, the battery with less remaining power is reduced within a certain range The rotational speed of the driving motor **560** corresponding to the component **555**, thereby reducing the power of the driving motor **560** and the power consumption of the battery assembly **555**, until the remaining power of the three groups of electric tools **100** reaches an equilibrium level or there is a set of power between the three groups of battery components **555**. Set the difference value, the energy management system **562** controls the three groups of electric tools **100** to output according to the same output power. While ensuring the use effect of the electric tool **100**, it accurately monitors the discharge of each battery assembly **555**, and according to the power of the battery assembly **555** Loss, the power of the drive motor **560** is controlled, and the working time of the electric tool **100** is maximized.

(154) As shown in FIGS. **31-33**, the energy management system **562** of the present invention is provided with an energy control unit **556** for collecting information about the use state of the electric tool **100** and an energy management unit **559** for issuing control instructions to the use of the electric tool **100** according to the use state information. So that the energy management system **562** can accurately collect and control the power consumption of the battery assembly **555** corresponding to each electric tool **100**, and can adjust the use state of the electric tool **100** according to changes in the use state information to ensure that the power tool **100** is The loss of the battery assembly **555** corresponding to each power tool **100** is roughly the same. While ensuring the working efficiency of the power tool **100**, it also improves the life time of garden tools using the energy management system **562** and the energy management method, so that it has a higher use. Efficiency and a good user experience.

(155) As shown in FIG. **34**, the present invention further provides an electric tool **100**, which includes a housing **567**, a power supply assembly **565** and a driving assembly **569** housed in the housing **567**, and a working assembly **531** and a walking assembly **566** connected to the housing **567**. Where the power supply component **565** is used to provide power to the drive component **569**, and the drive component **569** is used to drive the working component **531** and the walking component **566**, so that the electric tool **100** can move in the working area and complete the corresponding garden through the working component **531** Tasks of the working group. The working component **531** and the walking component **566** can also be defined as power consumption units.

(156) As shown in FIGS. **34-35**, the power supply assembly **565** includes a battery pack **539**, a battery pack compartment **568** for accommodating the battery pack **539**, and a sensor **570a**. One or more battery packs **539** can be provided, and each battery pack **539** can work independently, or can be connected in series or in parallel to realize the output of electric energy.

(157) As shown in FIG. **34**, the battery pack compartment **568** is connected to the housing **567**. The battery pack compartment **568** is provided with a plurality of positions (not labeled) for electrically connecting the battery pack **539**, and the plurality of positions are arranged in a regular

arrangement to be effective the size of the power supply assembly **565** is reduced to realize the miniaturization of the electric tool **100**, and in the present invention, the battery pack **539** and the battery pack compartment **568** are detachably connected.

(158) As shown in FIG. **35**, the sensor **570a** includes a first sensor **570b** connected to the output circuit of the power supply assembly **567** and a second sensor **570c** electrically connected to each position. In the present invention, the sensor **570a** is used to obtain the charging and discharging parameters of the power supply component **565**. It is defined that the maximum number of battery packs **539** that can be connected in the power supply component **565** is N , and the number of battery packs **539** that are actually connected in the power supply component **565** is n , And $n \leq N$, the charge and discharge parameters include at least the acceptable charge capacity Q of n battery packs **539**, the discharge rate C of each battery pack **539** in the n battery packs **539**, and the power SOC, and in the present invention, the charge power Q is obtained by calculating at least the discharge rate C and the power SOC of n battery packs **539**.

(159) As shown in FIG. **35**, the charging and discharging parameters also include the total current size and the total current direction of the power supply component **565** obtained by the first sensor **570b**, and the sub-current size of the battery pack **539** connected to the power supply component **565** obtained by the second sensor **570c**; Sub-current direction, voltage, temperature, fault information, remaining power and other parameters related to the performance of the battery pack **539**; and the discharge rate C and power SOC are also acquired by the second sensor **570c**.

(160) As shown in FIG. **35**, the driving assembly **569** includes a first motor **31** drivingly connected to the working assembly **531** and a second motor **32** drivingly connected to the walking assembly **566**. In a preferred embodiment of the present invention, the first motor **31** is simultaneously There are multiple, and the second motor **32** is provided with multiple at the same time, and is arranged in a one-to-one correspondence with the traveling wheels **51** in the traveling assembly **566**.

(161) As shown in FIG. **36**, the electric tool **100** further includes a power management unit **570**, which includes a power control module **572**, a battery pack management module **571** and a feedback current management module **573** electrically connected to the power control module **572**, respectively.

(162) As shown in FIG. **36**, the battery pack management module **571** is electrically connected to the power supply component **565** to obtain the charging and discharging parameters of the power supply component **565**; the feedback current management module **573** is electrically connected to the driving component **569** to obtain the power supply component **569** For feedback information, the power control module is used to receive charging and discharging parameters and feedback information, and controlling the driving component **569** to reverse charge the power supply component **565** according to the charging and discharging parameters and the feedback information, or to directly release the feedback current through the driving component **569**.

Wherein, the feedback information includes at least the feedback power AH generated when the first motor **31** and the second motor **32** in the driving assembly **569** decelerate/overspeed.

(163) As shown in FIGS. **35-37**, the feedback current management module **573** is electrically connected to the second sensor **570c** to obtain the feedback information of the driving component **569**; the output circuit is connected to the power control module **572**, and can be connected to the power control module **572**. Turn on/off under the control of **572**; the feedback information in the present invention also includes the feedback current I and the feedback time T , and the feedback power AH is at least related to the feedback current I and the feedback time T .

(164) As shown in FIGS. **35-37**, the walking assembly **566** of the electric tool **100** has three feedback braking situations during operation. One is that the speed of the second motor **32** corresponding to the walking assembly **566** exceeds the speed provided by the electric tool **100**. Maximum speed. At this time, the second motor **32** can directly feed back electrical energy to the power supply component **565** through the feedback circuit in the feedback current management module **573**, and at the same time provide electromagnetic torque for braking, which may occur

when going downhill, for example.

(165) As shown in FIGS. 35-37, another situation occurs during the deceleration of the walking assembly 566 during normal driving. At this time, the second motor 32 is in the power generation state to generate feedback current, and the feedback circuit feeds back part of the feedback current to the power supply assembly. 565, and continuously charge the power supply component 565 during this process. The third feedback braking situation is that when the second motor 32 is powered off, the working assembly 531 continues to rotate under the action of inertia. At this time, the second motor 32 will also generate feedback current, that is, in the present invention, the feedback power AH is at least It is jointly determined by the aforementioned three regenerative braking situations.

(166) As shown in FIGS. 35-37, the power control module 572 is used to receive the charging power Q and the feedback power AH, and determine the magnitude of the charging power Q and the feedback power AH, to control the driving component 569 to reverse the power supply component 565 The consumption of the feedback power AH is realized directly by charging or by driving the component 569.

(167) As shown in FIGS. 35-37, the maximum number of battery packs 539 that can be connected in the power supply component 565 is defined as N, and the number of battery packs 539 that are actually connected in the power supply component 565 is n, and $n \leq N$, then the charging power Q is defined by The number n of battery packs connected in the power supply component, the discharge rate C of each battery pack connected, and the power SOC are calculated and obtained by the electric energy control module 572. When N battery packs 539 are connected to the power supply component 565 at the same time, the power supply component 565 has the maximum charging power Q_{max} .

(168) As shown in FIGS. 35-37, when the second motor 32 is in a decelerating/overspeeding state and the first motor 31 and/or the second motor 32 generates feedback current, the power control module 572 controls the charging power Q and the maximum charging power Q_{max} . And the feedback power AH is calculated and compared. Further, when the charging power $Q \geq$ the feedback power AH, the power control module 572 uses the driving component 569 to reversely charge the n battery packs 539, and according to the power of each battery pack 539 The SOC controls the charging time of the battery pack 539 to avoid overcharging the battery pack 539.

(169) As shown in FIGS. 35-37, when the charging power $Q \leq$ the feedback power AH $\leq$ the maximum charging power $Q_{sub.max}$, the power control module 572 controls the battery pack 539 in the released state in the power supply component 565 to be connected, so that the adjusted charging power $Q' \geq$ return power AH; then the power control module 572 uses the drive component 569 to reversely charge each battery pack 539 in the power supply component 565; similarly, the power control module 6 can still charge each battery pack according to each battery pack in the process. The power SOC of 539 controls the charging time of the battery pack 539 to prevent the battery pack 539 from overcharging.

(170) As shown in FIGS. 35-37, when the charging power $Q <$ the maximum charging power is $Q_{sub.max} <$ the feedback power AH, the power control module 572 realizes the release of the feedback power AH through the driving component 569; or the power control module 572 controls N batteries All the packs 539 are connected to the power supply component 565, and the N battery packs 539 are reversely charged through the drive component 569 until the charging power $Q =$ the maximum charging power is $Q_{sub.max}$, the power control module 572 controls the drive component 569 to stop supplying power The component 565 supplies power, and the remaining feedback power AH is released through the driving component 569.

(171) As shown in FIGS. 35-37, a switch member 569 is provided in the second motor 32, and the switch member 569 is in control connection with the power control module 572, and the switch member 569 can be turned on under the control of the power control module 572, and the first motor The feedback current I or the remaining feedback power AH generated by a motor 31 and/or

the second motor 32 is released through the motor internal resistance of the second motor 32.

(172) As shown in FIGS. 35-37, only the power control module 572 is used to control the power supply assembly 565 to connect to the battery pack 539 in the released state, so that the feedback current I can be fully or partially acted on the battery pack 539. It also improves the utility of the power tool 100. In fact, the power control module 572 can also control the battery pack 539 in the power supply assembly 565 to release according to the charge power Q and the feedback power AH, so that the battery pack connected to the power supply assembly 565 The power of 539 is in an equilibrium state, and during this process, the power control module 572 can evaluate the remaining power of each battery pack 539 connected to the battery pack compartment 568 to release the fully charged battery pack 539.

(173) As shown in FIGS. 35-37, in the foregoing description, only the number n of battery packs 539 connected to the power supply assembly 565 is used as an example. In fact, the calculation of the number n of battery packs by the power control module 572 is also related to the battery pack The temperature t of 539 is related to the power SOC. Specifically, taking the temperature $t=40^{\circ}\text{C}$. as an example, the power control module 572 detects that the charging power $Q<$ the feedback power AH, and the feedback current $I\leq 2$ times the discharge rate C, and the power control When the module 572 evaluates that the power SOC of the power supply component 565 is greater than or equal to 90%, the power control module 572 will connect two battery packs 539 to the feedback circuit at the same time to receive the feedback current I. If the battery pack is available at this time The number of 539 $n<2$, the power control module 572 can alarm, and control the power tool 100 to take a speed-down action, the switch member 569 in the second motor 32 is turned on, so that the feedback power AH is consumed on the internal windings of the second motor 32, Does not feed back to the power supply component 565, so as to ensure the safety of the battery pack 539.

(174) Please refer to Table 1, which shows the feedback current I of the power supply component 565 and the driving component 569, the discharge rate C of the battery pack 539, and the number of battery packs 539 during the use of the power management unit 570 in a preferred embodiment of the present invention. n. The relationship between the temperature t of the battery pack 539 and the power SOC:

(175) TABLE-US-00001 TABLE 1 Temp. Feedback t Current I Power SOC $\geq 90\%$ Power SOC $\geq 50\%$ Power SOC $\geq 30\%$ Power SOC $\geq 20\%$ 40°C . $I\leq 2C$ $n\geq 2$ $n\geq 1$ $n\geq 1$ $n\geq 1$ $2C<I\leq 4C$ $n\geq 3$ $n\geq 2$ $n\geq 2$ $n\geq 2$ $4C<I\leq 8C$ $n\geq 5$ $n\geq 4$ $n\geq 4$ $n\geq 4$ $8C<I\leq 12C$ $n\geq 6$ $n\geq 5$ $n\geq 5$ $n\geq 5$ When $I>$ When $I>12C$, all When $I>12C$, all When $I>12C$, all When $I>12C$, all 12C, then N battery packs 539 N battery packs 539 N battery packs 539 N battery packs 539 the feedback are connected, and are connected, and are connected, and are connected, and time T > when the feedback when the feedback when the feedback when the feedback 100 ms, or time T > 100 ms, the time T > 100 ms, the time T > 100 ms, the time T > 100 ms, the the quantity power control power control power control of battery module 572 module 572 module 572 module 572 packs 539 is controls the drive controls the drive controls the drive controls the drive insufficient component 569 to component 569 to component 569 to component 569 to cease providing cease providing cease providing cease providing power to the power power to the power power to the power power to the power supply component supply component supply component supply component 565. The release of 565. The release of 565. The release of 565. The release of the remaining the remaining the remaining the remaining feedback power AH feedback power AH feedback power AH feedback power AH through the drive through the drive through the drive through the drive component 569 is component 569 is component 569 is component 569 is thus realized, and thus realized, and thus realized, and thus realized, and the power the power the power the power the power management unit management unit management unit management unit 570 issues a power 570 issues a power 570 issues a power 570 issues a power down command. down command. down command. down command. 25°C . $I\leq 2C$ $n\geq 2$ $n\geq 1$ $n\geq 1$ $n\geq 1$ $2C<I\leq 4C$ $n\geq 3$ $n\geq 2$ $n\geq 2$ $n\geq 2$ $4C<I\leq 8C$ $n\geq 5$ $n\geq 4$ $n\geq 4$ $n\geq 4$ $8C<I\leq 12C$ $n\geq 6$ $n\geq 5$ $n\geq 5$ $n\geq 5$ When $I>$ When $I>$

12C, all When $I > 12C$, all When $I > 12C$, all When $I > 12C$, all 12C, then N battery packs 539 N battery packs 539 N battery packs 539 N battery packs 539 the feedback are connected, and are connected, and are connected, and are connected, and time $T >$ when the feedback when the feedback when the feedback 100 ms, or time $T > 100$ ms, the time $T > 100$ ms, the time $T > 100$ ms, the the quantity power control power control power control power control of battery module 572 module 572 module 572 module 572 packs 539 is controls the drive controls the drive controls the drive controls the drive insufficient component 569 to component 569 to component 569 to component 569 to cease providing cease providing cease providing cease providing power to the power power to the power power to the power power to the power supply component supply component supply component supply component supply component 565. The release of 565. The release of 565. The release of 565. The release of the remaining the remaining the remaining the remaining feedback power AH feedback power AH feedback power AH feedback power AH through the drive through the drive through the drive through the drive component 569 is component 569 is component 569 is component 569 is thus realized, and thus realized, and thus realized, and the power the power the power the power management unit management unit management unit management unit 570 issues a power 570 issues a power 570 issues a power 570 issues a power down command. down command. down command. down command. $0^{\circ}C$. $I \leq 2C$ $n \geq 6$ $n \geq 3$ $n \geq 3$ $n \geq 3$ $2C < I \leq 4C$ $n \geq 6$ $n \geq 4$ $n \geq 4$ $n \geq 4$ $4C < I \leq 8C$ $n \geq 6$ $n \geq 5$ $n \geq 5$ $n \geq 5$ When $I >$ When $I > 8C$, all N When $I > 8C$, all N When $I > 8C$, all N When $I > 8C$, all N 8C, then the battery packs 539 battery packs 539 battery packs 539 battery packs 539 feedback are connected, and are connected, and are connected, and are connected, and time $T >$ when the feedback when the feedback when the feedback when the feedback 100 ms, or time $T > 100$ ms, the time $T > 100$ ms, the time $T > 100$ ms, the time $T > 100$ ms, the the quantity power control power control power control power control of battery module 572 module 572 module 572 module 572 packs 539 is controls the drive controls the drive controls the drive controls the drive insufficient component 569 to component 569 to component 569 to component 569 to cease providing cease providing cease providing cease providing power to the power power to the power power to the power power to the power supply component supply component supply component supply component supply component 565. The release of 565. The release of 565. The release of 565. The release of the remaining the remaining the remaining the remaining feedback power AH feedback power AH feedback power AH feedback power AH through the drive through the drive through the drive through the drive component 569 is component 569 is component 569 is component 569 is thus realized, and thus realized, and thus realized, and thus realized, and the power the power the power the power management unit management unit management unit management unit 570 issues a power 570 issues a power 570 issues a power 570 issues a power down command. down command. down command. down command. $-10^{\circ}C$. $I \leq 2C$ $n \geq 6$ $n \geq 4$ $n \geq 4$ $n \geq 4$ When $I >$ When $I > 2C$, all N When $I > 2C$, all N When $I > 2C$, all N When $I > 2C$, all N 2C, then the battery packs 539 battery packs 539 battery packs 539 battery packs 539 feedback are connected, and are connected, and are connected, and are connected, and time $T >$ when the feedback when the feedback when the feedback when the feedback 100 ms, or time $T > 100$ ms, the time $T > 100$ ms, the time $T > 100$ ms, the time $T > 100$ ms, the the quantity power control power control power control power control of battery module 572 module 572 module 572 module 572 packs 539 is controls the drive controls the drive controls the drive controls the drive insufficient component 569 to component 569 to component 569 to component 569 to cease providing cease providing cease providing cease providing power to the power power to the power power to the power power to the power supply component supply component supply component supply component supply component 565. The release of 565. The release of 565. The release of 565. The release of the remaining the remaining the remaining the remaining feedback power AH feedback power AH feedback power AH feedback power AH through the drive through the drive through the drive through the drive component 569 is component 569 is component 569 is component 569 is thus realized, and thus realized, and thus realized, and thus realized, and the power the power the power the power management unit management unit management unit management unit 570 issues a power 570 issues a power 570 issues a power 570 issues a power down command. down command. down command. down command.

realized, and thus realized, and the power the power the power the power management unit management unit management unit management unit 570 issues a power 570 issues a power 570 issues a power 570 issues a power down command. down command. down command. down command.

(176) As shown in FIGS. **35-37**, the power control module **572** estimates that the power SOC of the power supply component **565** is greater than or equal to 90% as an example for illustration. In other embodiments of the present invention, the power SOC may also be 50% or 30% and 20%. The smaller the power SOC, the greater the charging power Q of the power supply component **565**. At this time, the larger the number n of battery packs **539** that need to be connected to the power supply component **565**. At this time, only the charging power Q needs to be guaranteed. Feed back the power AH.

(177) In this specification and the accompanying drawings, the electric tool **100** is an electric lawn mower as an example for illustration. In other embodiments of the present invention, the electric tool **100** may also be an electric drill, a chain saw, a table saw, or a lawn mower. Lawn trimmers, hair dryers, etc. are commonly used electric tools that also have a power supply component **565**, a drive component **569**, and an electric power management unit **570**.

(178) As shown in FIGS. **34-37**, the electric tool **100** of the present invention is provided with an electric power control assembly **570** connected to the power supply assembly **565** and the drive assembly **569** respectively, and can automatically and timely be in position according to the state of the battery pack **539** in the electric tool **100**. The battery pack **539** in the released state is connected to the feedback circuit to jointly absorb the feedback current I generated by the driving component **569** to prevent a single battery pack **539** from being overcharged, thereby prolonging the life of the battery pack **539** and providing feedback current to the driving component **569**. While effective utilization and release of I, the working efficiency of the electric tool **100** is improved.

(179) As shown in FIG. **38**, the present invention provides a battery component management device for controlling a number of battery components **555** to work in parallel to supply power to a load **579**. The battery assembly management device includes a battery compartment **574** for accommodating the battery assembly **555**, a control assembly **572**, and an output branch **578**.

(180) As shown in FIG. **38**, the battery compartment **574** is provided with at least two battery interfaces **575**. Each battery interface **575** is used to connect to the battery assembly **555**, and the battery assembly **555** connected to it forms a power supply branch **576**. In practical applications, the number of the battery interfaces **575** can be set as required. The specifications of the multiple battery assemblies **555** connected to the battery interface **575** may be the same or different. Each power supply branch **576** is further provided with a switch **577**, and the other end of the switch **577** is connected to the output branch **578**, so that the power supply branch **576** and the output branch **578** are controlled by the switch **577**. Between on and off. In this embodiment, the switch **577** is a switch tube. The control component **572** includes a power detection unit **580** to detect the power of the battery component **555**, a voltage detection unit **581** to detect the voltage of the battery component **555**, and a current detection to detect the current of the power supply branch **576** and the output branch **578**. Unit **582** and control unit **583**.

(181) As shown in FIG. **38**, during use, the control unit **583** obtains the internal information of the battery assembly **555** through the battery interface **575**, and determines whether the battery assembly **555** is abnormal according to the internal information. If the battery assembly **555** is abnormal, the control unit **583** controls the power supply branch **576** corresponding to the battery assembly **555** to stop working, and sends an alarm message to notify the user of the abnormal battery assembly **555**. The abnormality may be the lack of a single cell in the battery assembly, the voltage of the single cell or battery pack is too high, the voltage of the single cell or the battery pack is too low, the temperature of the single cell or the battery pack is too high, and so on. In this embodiment, the control unit **583** controls whether the power supply branch **576** works by controlling the switch **577**. The control unit **583** controls the power detection unit **580** to work to

detect the power of the battery assembly 555 corresponding to each power supply branch 576. If the number of battery components 555 whose power is greater than the first power threshold $Q_{sub.1}$ is not less than N_1 , the control unit 583 directly or indirectly controls the upper limit of the output current of each battery component 555 to the rated current $I_{sub.m}$ of the battery component 555. If the number of battery components 555 with power greater than the first power threshold $Q_{sub.1}$ is less than N_1 , and the number of battery components 555 with power greater than the second power threshold $Q_{sub.2}$ is not less than $N_{sub.2}$, the control unit 583 directly or indirectly controls each battery The upper limit of the output current of the component 555 is $k_{sub.1} * I_{sub.m}$. If the number of battery components 555 whose power is greater than the second power threshold $Q_{sub.2}$ is less than N_3 , the control unit 583 directly or indirectly controls the upper limit of the output current of each battery component 555 to $k_{sub.2} * I_{sub.m}$, where $Q_{sub.1} > Q_{sub.2}$, $0 < k_{sub.2} < k_{sub.1} < 1$. The direct control means that the control unit 583 reduces the current output or the upper limit of the current output of the power supply branch 576 by controlling the duty cycle of the control signal of the switch 577. The indirect control means that the control unit 583 sends a current limit signal to the load 579, so as to indirectly achieve the purpose of reducing the upper limit of the output current of the battery assembly 555 by means of the load 579 self-limiting power. The first power threshold $Q_{sub.1}$ and the second power threshold $Q_{sub.2}$ may refer to power or a percentage of power. The $N_{sub.1}$, $N_{sub.2}$, $N_{sub.3}$, $k_{sub.1}$, and $k_{sub.2}$ can be set as required. For example, $N_{sub.1}$ is set to 4, $N_{sub.2}$ is set to 2, $N_{sub.3}$ is set to 2, $k_{sub.1}$ is set to 60%, and $k_{sub.2}$ is set to 50%. This arrangement can effectively prevent the battery assembly 555 from being over-discharged, thereby protecting the battery assembly 555 and prolonging the service life of the battery assembly 555.

(182) As shown in FIG. 38, the control unit 583 determines the priority level of each power supply branch 576 according to the level of power, and then controls the power supply branch 576 with the highest priority to supply power to the load 579. When the difference between the power of the currently working battery component 555 and the power of the battery component 555 of the power supply branch 576 corresponding to the next priority level is within the first power range, the control unit 583 controls the power supply branch corresponding to the next priority level 576 works, and is connected in parallel with the currently working power supply branch 576 to supply power to the load 579. The size of the first power interval can be set as needed. Of course, in other embodiments, the control unit 583 may also determine the priority level of each power supply branch 576 according to the percentage of power, and then control the power supply branch 576 with the highest priority to supply power to the load 579; the power percentage It is the ratio of the current power of the battery assembly 555 to the rated power. When the difference between the power percentage of the battery component 555 currently working and the power percentage of the battery component 555 of the power supply branch 576 corresponding to the next priority level is within the first proportional interval, the control unit 583 controls the power supply corresponding to the next priority level The branch 576 works, and is connected in parallel with the currently working power supply branch 576 to supply power to the load 579. The size of the first ratio interval can be set as required. Of course, it is understandable that the control unit 583 can also determine the priority level of each power supply branch 576 according to the voltage level, and then control the power supply branch 576 with the highest priority level to supply power to the load 579; When the difference between the voltage of the battery assembly 555 and the voltage of the battery assembly 555 of the power supply branch 576 corresponding to the next priority level is within the first voltage interval, the control unit 583 controls the power supply branch 576 corresponding to the next priority level to work, and It is connected in parallel with the currently working power supply branch 576 to supply power to the load 579. The first voltage interval may be 3V-5V. Of course, the range of the first voltage interval can also be set as needed.

(183) As shown in FIG. 38, when the voltage detection unit 581 detects that the voltage of the battery assembly 555 is greater than the overvoltage value or less than the undervoltage value, the

control unit **583** controls the power supply branch **576** corresponding to the battery assembly **555**. The switch **577** is turned off, so that the power supply branch **576** corresponding to the battery assembly **555** stops working, thereby protecting the battery assembly **555**.

(184) As shown in FIG. **38**, when the current detection unit **582** detects that the current of the power supply branch **576** is greater than the first current threshold or less than the second current threshold, the control unit **583** controls the power supply branch **576** to stop working to protect the power supply branch **576** corresponds to the battery assembly **555** and the load **579**. The first current threshold is the maximum current allowed by the power supply branch **576**. The second current threshold value is the minimum current value allowed by the power supply branch **576**, and is usually set to zero. When the current of the power supply branch **576** is less than zero, the battery assembly **555** corresponding to the power supply branch **576** is in a charging state.

(185) As shown in FIG. **38**, the control unit **583** also detects the number N of battery assemblies **555** currently operating. The current detection unit **582** also detects the current of the output branch **578**, that is, the total current I output by all the battery assemblies **555** currently working. If $I > (N \cdot I_m + \Delta I)$, the control unit **583** directly or indirectly controls the battery assembly **555** to reduce the output current, wherein the current offset $[\Delta I]$ is set in advance. When $I > (N \cdot I_m + \Delta I)$ and exceeds a preset time threshold, the control unit **583** directly or indirectly controls the battery assembly **555** to reduce the current output.

(186) As shown in FIG. **38**, the battery component management device of the present invention can intelligently limit the output current of the battery component **555** or intelligently switch the working mode of the load **579** according to the power and quantity of the battery component **555**, thereby extending the load. The working time of **579** avoids the disadvantages of excessive use of the battery assembly **555**, thereby protecting the battery assembly **555**, prolonging the service life of the battery assembly **555**, and improving the overall working efficiency of the load **579**.

(187) As shown in FIG. **39**, the present invention also provides a battery component management method for controlling a number of battery components **555** to work in parallel to supply power to the load **579**. The battery component management method includes the following steps: **S0**: Detect whether the battery component corresponding to the power supply branch is abnormal; if the battery component is abnormal, close the power supply branch corresponding to the battery component. **S1**: Detect the power of the battery component corresponding to each power supply branch. **S2**: determining a first power is greater than the threshold quantity Q of the battery pack. N_1 is the number N is not less than N_1 ; if yes, control component directly or indirectly controls the output current limit for each battery module rated current I_m of the battery pack; otherwise, Go to step **S3**. **S3**: Judging whether the number of battery components whose power is greater than the second power threshold Q_2 is not less than N_2 ; if so, the control component directly or indirectly controls the upper limit of the output current of each battery component to $k_1 \cdot I_m$; where $Q_1 > Q_2$, $0 < k_1 < 1$. **S4**: Determine whether the number of battery components with a power greater than the second power threshold Q_2 is less than N_3 ; if so, the control component directly or indirectly controls the upper limit of the output current of each battery component to $k_2 \cdot I_m$, where $0 < k_2 < k_1 < 1$.

(188) As shown in FIG. **40**, the step **S1** further includes the following steps: **S11**: Detect the power of the battery component corresponding to each power supply branch; **S12**: Determine the priority level of each power supply branch according to the level of power; **S13**: Control the power supply branch with the highest priority to supply power to the load; **S14**: When the difference between the power of the currently working battery component and the power of the battery component of the power supply branch corresponding to the next priority level is within the first power range, control the power supply branch corresponding to the next priority level to work, and compare it to the current work. The power supply branches are connected in parallel to supply power to the load.

(189) As shown in FIG. **41**, in other embodiments, the step **S1** may also be: **S11'**: Detect the percentage of power of the battery assembly corresponding to each power supply branch; **S12'**:

Determine the priority level of each power supply branch according to the percentage of electricity; **S13'**: Control the power supply branch with the highest priority to supply power to the load; **S14'**: When the difference between the power percentage of the battery component currently working and the power percentage of the battery component of the power supply branch corresponding to the next priority level is within the first proportional interval, control the power supply branch corresponding to the next priority level to work, and it is connected in parallel with the current working power supply branch to supply power to the load.

(190) As shown in FIG. 42, the step **S1** may also be: **S11''**: Detect the voltage of the battery component corresponding to each power supply branch; **S12''**: Determine the priority level of each power supply branch according to the voltage level; **S13''**: Control the power supply branch with the highest priority to supply power to the load; **S14''**: When the difference between the voltage of the currently working battery component and the voltage of the battery component of the power supply branch corresponding to the next priority level is within the first voltage interval, control the power supply branch corresponding to the next priority level to work and compare it with the current the working power supply branches are connected in parallel to supply power to the load.

(191) As shown in FIG. 43, the present invention also discloses an electric tool **100**, including a traveling mechanism **12**, an operating mechanism **531**, a control mechanism (not shown) that controls the operation of the traveling mechanism **12** and the operating mechanism **531**, and a number of battery assemblies **555** And the battery assembly management device. In this embodiment, the operating mechanism **531** may be a mowing component, but in other embodiments, the operating mechanism **531** may also be other functional components. In this embodiment, the control mechanism controls the walking mechanism **12** and the operating mechanism **531** at the same time. However, in other embodiments, a walking control mechanism for controlling the walking mechanism **12** and the operation of the operating mechanism **531** may be separately provided. Control agency. The battery assembly management device controls the plurality of battery assemblies **555** to work together in parallel to supply power to the traveling mechanism **101** and the operating mechanism **102**. When the number of battery assemblies **555** whose power is greater than the first power threshold $Q_{sub.1}$ is not less than $N_{sub.1}$, the control unit **583** sends a performance priority signal to the control mechanism, and the control mechanism does not respond to the traveling mechanism **101** and the operating mechanism **102**. As a limit, the traveling mechanism **101** can travel at a maximum speed $V_{sub.m}$, and the operating mechanism **102** can perform work at a maximum rotation speed $R_{sub.m}$. At this time, the electric tool **100** is in the performance priority mode, that is, the first state, which can cope with the complex and heavy-duty grass conditions. When the number of battery components **555** whose power is greater than the first power threshold $Q_{sub.1}$ is less than $N_{sub.1}$, and the number of battery components **555** whose power is greater than the second power threshold $Q_{sub.2}$ is not less than $N_{sub.2}$, the control unit **583** sends a current limiting signal to the A control mechanism, the control mechanism controls the walking mechanism **12** and the operating mechanism **531** to run at a mid-range speed. At this time, the maximum operating speed of the walking mechanism **12** is $k_{sub.3} * V_{sub.m}$, and the maximum rotational speed of the operating mechanism **531** is $k_{sub.4} * R_{sub.m}$, so that the output current of the battery assembly **555** is not greater than the upper limit $k_{sub.1} * I_{sub.m}$. At this time, the electric tool **100** is in the energy-saving mode, that is, the second state, which can cope with lighter grass conditions. When the number of battery assemblies **555** whose power is greater than the second power threshold $Q_{sub.2}$ is less than $N_{sub.3}$, the control unit **583** sends a current limiting signal to the control mechanism, and the control mechanism controls the walking mechanism **12** and the operating mechanism **531** to operate at low gears. At this time, the maximum operating speed of the traveling mechanism is $k_{sub.5} * V_{sub.m}$, and the maximum rotational speed of the operating mechanism **531** is $k_{sub.6} * R_{sub.m}$, so that the output current of the battery assembly **555** does not exceed the upper limit $k_{sub.2} * I_{sub.m}$. At this time, the electric tool **100** is in the super energy-saving mode, that is, the third state, which can cope with simple

grass conditions. In this embodiment, the number of the battery assembly 555 is, for example, 6, the Q.sub.1 is 50%, the Q.sub.2 is 20%, the N.sub.1 is 4, and the N.sub.2 and N.sub.3 are 2. The k.sub.3 and k.sub.4 are 0.6, and the k.sub.5 and k.sub.6 are 0.6. Of course, the values of Q.sub.1, Q.sub.2, N.sub.1, N.sub.2, N.sub.3, k.sub.3, k.sub.4, k.sub.5, and k.sub.6 can also be set as required.

(192) As shown in FIG. 43, when the number of battery assemblies 555 whose power is greater than the second power threshold Q2 is less than N.sub.3, the electric tool 100 is controlled to be in the third state; it can also be set as: when the power is greater than the third power threshold Q.sub.3. When the number of battery assemblies 555 is less than N.sub.3, the electric tool 100 is controlled to be in the third state, where: $Q_{sub.3} \leq Q_{sub.2}$.

(193) Therefore, the battery component management device of the present invention can intelligently switch the working mode of the load according to the power and quantity of the battery components, thereby prolonging the working time of the load, avoiding the abuse of battery components being overused, and improving the overall working efficiency of the load.

(194) As shown in FIG. 44, the present invention discloses a charger 585, which includes at least two charging ports 584 and a control component 572 for controlling the charging ports 584.

(195) As shown in FIG. 44, the charging interface 584 is used to connect a battery assembly 555 (or a power supply unit) of the same specification to be charged, and the battery assembly 555 connected to it forms a charging circuit. The battery assembly 555 can be a single battery or a battery pack composed of multiple single batteries. The charging circuit is provided with a switch (not shown) to be turned on or off under the control of the control component 572. The switch can be a MOS tube, a relay, and so on. Each of the charging circuits has a corresponding priority level and a level status corresponding to the priority level. The priority level is used to indicate the priority charging sequence of the charging circuit among all charging circuits. Usually, you can use a number to indicate the priority level. For example, suppose a charger has three charging ports A, B, and C, and set the priority level of the charging circuit corresponding to the charging port B to 1, the priority level of the charging circuit corresponding to the charging port A to 2, and the charging port corresponding to the C charging port. The priority level of the charging circuit is 3; when the charger is working, the charger first charges the battery component connected to the charging port B, then the battery component connected to the charging port A, and finally the battery component connected to the charging port C. Charging, where the numbers 1, 2, and 3 indicate the priority levels of the charging circuits corresponding to the A, B, and C charging ports. Of course, it is understandable that there are many ways to express the priority levels, which will not be listed here. The control component 572 obtains the status information of the battery component 555 corresponding to each charging circuit before charging, and determines the priority level of the corresponding charging circuit and the level status corresponding to the priority level according to the status information of the battery component 555. The control component 572 communicates with the battery component 555 through a CAN bus or a serial port and obtains status information of the battery component 555. The status information is the remaining power of the battery assembly 555 before charging or the voltage before charging. The level state may be the remaining power of the battery assembly 555 before charging, or the ratio of the remaining power of the battery assembly 555 before charging to the capacity of the battery assembly 555. Of course, it is understandable that the level state may also be the voltage before the battery assembly 555 is charged, or the ratio of the voltage before the battery assembly 555 is charged to the voltage when the battery assembly 555 is fully charged. For example, suppose a charger has three charging ports A1, B1, and C1, and it charges A1 battery pack, B1 battery pack, and C1 battery pack respectively. The remaining power of A1 battery pack is 40% of the total power. The remaining power is 20% of the total power, and the remaining power of the C1 battery pack is 60% of the total power, then the priority level corresponding to the B1 charging interface is 1, and the corresponding level status is 20%; the priority level corresponding to the A1 charging interface If it is 2, the corresponding level

status is 40%; the priority level corresponding to the C1 charging interface is 3, and the corresponding level status is 60%. In this embodiment, each priority level corresponds to one charging interface **30** or charging circuit, but in other embodiments, it can also be set as a priority level corresponding to multiple charging interfaces **30** or charging circuits. In this case, the priority level corresponds to Multiple charging ports **30** or charging circuits work at the same time. For example, when the level states corresponding to any two charging circuits are the same, the priority levels corresponding to the two charging circuits are set to be the same. Of course, in other embodiments, the status information and level status information can also be represented by the time required for the battery assembly **555** to be fully charged.

(196) As shown in FIGS. **44-45**, the control component **572** sequentially controls the operation of the corresponding charging loops according to the priority order. When the currently working charging circuit charges the corresponding battery component **555** to the level state corresponding to the next priority level, the control component **572** controls the charging circuit corresponding to the next priority level to work together with the currently working charging circuit, and so on, Until all the charging circuits are in working state, so as to charge the battery components **555** corresponding to the charging circuits to the full state at the same time. With this configuration, battery assemblies **555** of different power levels can be fully charged at the same time, thereby effectively avoiding problems such as overcharging of the battery pack and discharging of the battery pack during charging, thereby increasing the service life of the battery pack. For example, suppose a charger has three charging interfaces A2, B2, and C2, and respectively charge A2 battery packs with 40% status information, B2 battery packs with 20% status information, and C2 battery packs with 60% status information. The control component **572** obtains the status information of the A2, B2, and C2 battery packs, and sorts them from small to large, so as to determine that the priority level corresponding to the A2 battery pack is 2, the corresponding level status is 40%, and the B2 battery pack corresponds to The priority level is 1, the corresponding level status is 20%, the priority level corresponding to the C2 battery pack is 3, and the corresponding level status is 60%. Then, the control component **572** first controls the operation of the charging circuit corresponding to the B2 battery pack. When the B2 battery pack is charged to 40%, the control component **572** controls the charging circuit corresponding to the A2 battery pack to work with the charging circuit corresponding to the B2 battery pack. When the A2 or B2 battery pack is charged to 60%, the control component **572** controls the charging circuits corresponding to the A2, B2, and C2 battery packs to work at the same time to charge the A2, B2, and C2 battery packs to a fully charged state.

(197) As shown in FIGS. **44-45**, before controlling the operation of the charging circuit, the control component **572** obtains the internal information of the battery component **555** and determines whether the battery component **555** is abnormal. If the battery assembly **555** is abnormal, the control assembly **572** closes the charging circuit corresponding to the battery assembly **555** and sends an abnormal signal. The abnormality may be the lack of a single battery in the battery pack, the excessively high voltage of the single battery, and so on. The abnormal signal may be represented by an indicator light corresponding to the charging interface **584**. For example, the flashing indicator light can be used to indicate that the battery pack is abnormal. After the fault of the abnormal battery assembly **555** is eliminated, the control assembly **572** re-determines the priority level corresponding to each charging circuit. When the power or voltage of the battery component **555** after the fault is eliminated is less than the power or voltage of the battery component **555** corresponding to the currently working charging circuit, the control component **572** closes all the currently working charging circuits and controls the faulty The charging circuit corresponding to the battery assembly **555** works.

(198) As shown in FIGS. **44-45**, when the control component **572** controls the charging circuit to work, the control component **572** simultaneously detects the charging temperature of the battery component **555** corresponding to the charging circuit. If the charging temperature is abnormal, the

control component 572 controls the charging circuit to close, and at the same time sends out an abnormal reminder.

(199) As shown in FIGS. 46-47, the charger 585 is provided with a battery compartment 586 corresponding to the charging interface 584 and accommodating the battery assembly 555, and a battery compartment 586 for detecting whether the battery assembly 555 is in the battery compartment 586. Detection sensor (not shown). When the detection sensor detects the battery assembly 555 and the control assembly 572 cannot obtain the status information of the corresponding battery assembly 555, the charger 585 sends an abnormal signal to remind the user that the battery assembly 555 is not plugged in. The detection sensor may be a gravity sensor, a distance sensor, etc. installed in the battery compartment 586. The battery compartment 586 is provided with a conductive terminal group 587 and a positioning insert assembly 592, and the conductive terminal group 587 and the positioning insert assembly 592 are spaced apart from each other. The conductive terminal group 587 includes a pair of charging terminals 588, a communication terminal 590, and a charging positive electrode 589. The positioning insert assembly 592 includes a space 593 and a positioning insert 594. The battery compartment 586 determines the address through different combinations of the positions and numbers of the empty positions 593 and the positioning inserts 594. For example, the logical address of the battery compartment 5861 is 000, the logical address of the battery compartment 5862 is 585, the logical address of the battery compartment 5863 is 110, and the logical address of the battery compartment 5864 is 011. The battery assembly 555 is provided with a positioning slot assembly (not shown) that cooperates with the positioning insert assembly 592. The control component 572 determines the address of the battery component 555 according to the mating state of the positioning insert component 592 and the positioning socket component. Of course, it can be understood that, in other embodiments, the control component 572 can also dynamically assign an address to the charging interface 584 connected to the battery component 555 or the corresponding charging circuit.

(200) As shown in FIG. 48, the present invention also provides a charging control method, which includes the following steps: S1: Determine the priority level of each charging loop and the level status corresponding to the priority level. S2: Control the operation of the corresponding charging circuit in sequence according to the priority level, and charge the battery component corresponding to the current working charging circuit to the level state corresponding to the next priority level, and then control the charging circuit corresponding to the next priority level to the current working. The charging circuits work together, and so on, until all the charging circuits are in working state, so as to charge the battery components corresponding to all the charging circuits to a fully charged state.

(201) The step S1 also includes: detecting whether the battery assembly corresponding to the charging interface is abnormal; if the battery assembly is abnormal, closing the charging circuit corresponding to the battery assembly.

(202) The step S2 further includes: when the charging circuit is working, detecting the charging temperature of the battery assembly corresponding to the charging circuit; if the charging temperature is abnormal, closing the charging circuit corresponding to the battery assembly.

(203) Therefore, the charger 585 of the present invention can control the charging circuit positioning insert components of different priority levels to work together according to the priority levels, so that battery packs of different power levels can be fully charged at the same time, thereby effectively avoiding overcharging of the battery pack and battery during charging. Problems such as battery pack discharge, thereby increasing the service life of the battery pack.

(204) As shown in FIG. 44 and FIG. 49, the control component 572 sequentially controls the corresponding charging loops according to the priority order to charge the corresponding battery component 555 to the corresponding level state, and then controls the corresponding battery components in sequence according to the priority order again. The charging loop works to charge

the corresponding battery assembly 555 to the next corresponding level state, and so on, until all the battery assemblies 555 are in a fully charged state. For example, suppose a charger has three charging ports A1, B1, and C1. The priority levels are 2, 1, and 3 respectively, and the A1 battery pack, B1 battery pack, and C1 battery pack are charged respectively; the A1 charging port has 50%, There are three levels of 60% and 100%. The B1 charging interface has two levels of 70% and 100%. The C1 charging interface has a level of 100%. When the charger is working, the charger first sets the B1 of the B1 charging interface. Charge the battery pack to 70% of the total power, then charge the A1 battery pack of the A1 charging port to 50% of the total power, then charge the C1 battery pack of the C1 charging port to 100% of the total power, and then charge the B1 charging port to 100% of the total power. Charge the B1 battery pack to 100% of the total power, then charge the A1 battery pack of the A1 charging port to 60% of the total power, and finally charge the A1 battery pack of the A1 charging port to 100% of the total power. The control component 572 sequentially controls the corresponding charging loop to work once according to the priority order to charge the corresponding battery component 555 to a corresponding level state. This process is defined as a charging round.

(205) As shown in FIG. 49, before controlling the operation of the charging circuit, the control component 572 obtains the status information of the battery component 555 and determines whether the battery component 555 is abnormal. If the battery assembly 555 is abnormal, the control assembly 572 closes the charging circuit corresponding to the battery assembly 555, sends an abnormal signal, and kicks the charging interface 584 corresponding to the battery assembly 555 out of the current charging round. The abnormality may be the lack of a single battery in the battery pack, the excessively high voltage of the single battery, and so on. The abnormal signal may be represented by an indicator light corresponding to the charging interface 584. For example, the flashing indicator light can be used to indicate that the battery pack is abnormal. When the fault of the battery assembly 555 is eliminated, the control assembly 572 re-determines the priority level corresponding to each charging interface 584 and starts a new charging round. Of course, the control component 572 can also re-determine the priority levels of all the charging ports 584 after the charging round in the current priority order is completed.

(206) As shown in FIG. 49, the charger 585 is provided with a battery compartment (not shown) corresponding to the charging interface 584 and accommodating the battery assembly 555, and a detection sensor for detecting whether there is a battery assembly 555 in the battery compartment. When the detection sensor detects the battery assembly 555 and the control assembly 572 cannot obtain the status information of the corresponding battery assembly 555, the charger 585 sends an abnormal signal to remind the user that the battery assembly 555 is not plugged in. The detection sensor may be a gravity sensor, a distance sensor, etc. installed in the battery compartment.

(207) As shown in FIG. 49, when the control component 572 controls the charging circuit to work, the control component 572 also detects the charging temperature of the battery component 555 corresponding to the charging circuit at the same time; if the charging temperature is abnormal, the control The component 572 controls the charging circuit to close, sends an abnormal signal, and kicks the charging interface 584 corresponding to the charging circuit out of the current charging round.

(208) As shown in FIG. 49, each level status has a first level status value and a second level status value; the control component 572 first determines whether the battery component 555 corresponding to the charging interface 584 meets the first level status value; if the charging interface If the battery component 555 corresponding to 584 meets the first-level state value, the control component 572 closes the charging circuit corresponding to the charging interface 584; if the battery component 555 corresponding to the charging interface 584 does not meet the first-level state value, the control component 572 controls the operation of the charging circuit corresponding to the charging port 584 to charge the battery component 555 corresponding to the charging port 584 to the second level state value. It can be understood that the state value of the first level and the

state value of the second level may be equal or different. The following is an example. Assume that a battery pack has an A2 charging interface, a B2 charging interface, and a C2 charging interface, and the priority levels are 1, 2, and 3 respectively, and the A2 battery pack, the B2 battery pack, and the C2 battery pack are charged respectively. The A2 charging interface has a level A status and a level B status, the B2 charging interface has a level C status and a level D status, and the C2 charging interface has a level E status; the first level status value of the level A status is 50%, and the second level status value 60%; the first level status value and the second level status value of the B level status are 100%; the first level status value of the C level status is 80%, the second level status value is 90%; the D level status The first-level status value and the second-level status value are both 100%; the first-level status value and the second-level status value of the E-level status are both 100%.

(209) As shown in FIG. 50, the working sequence of the charger is as follows: **P1**: Determine whether the power of the A2 battery pack is less than 50%; if so, charge the power of the A2 battery pack to 60%, and then skip to step **P2**. **P2**: Determine whether the power of the B2 battery pack is less than 80%; if so, charge the power of the B2 battery pack to 90%, and then skip to step **P3**. **P3**: Determine whether the power of the C2 battery pack is less than 100%; if so, charge the power of the C2 battery pack to 100%, and then skip to step **P4**. **P4**: Determine whether the power of the A2 battery pack is less than 100%; if so, charge the power of the A2 battery pack to 100%, and then skip to step **P5**. **P5**: Determine whether the power of the B2 battery pack is less than 100%; if so, charge the power of the B2 battery pack to 100%.

(210) As shown in FIG. 51, the present invention also discloses a charging control method, which includes the following steps: **S1**: Determine the priority level of each charging loop and at least one level state corresponding to the priority level; **S2**: Control the corresponding charging circuits in sequence according to the priority order to charge the corresponding battery components to the corresponding level state; then control the corresponding charging circuits in sequence according to the priority order to charge the corresponding battery components to the next corresponding level Status, and so on, until all battery components are fully charged.

(211) The step **S1** also includes: detecting whether the battery assembly corresponding to the charging interface is abnormal; if the battery assembly is abnormal, closing the charging circuit corresponding to the battery assembly.

(212) The step **S2** further includes: after completing a charge in the priority order, that is, after completing a charge round, re-determining the priority level of each charging loop.

(213) As shown in FIG. 52, the present invention also discloses an electric tool **100**, which includes at least two battery assemblies **555** and a charging system. The battery assembly **555** is installed on the electric tool **100** and supplies power to the electric tool **100**. The charging system and the electric tool **100** may be arranged in a separate structure, or may be arranged in an integrated structure, that is, the charging system is fixedly installed on the electric tool **100**. The charging system includes at least two charging interfaces and control components that are matched with the battery assembly **555**. The structure of the charging interface and the control assembly and the mutual cooperation relationship are the same as those of the charging interface **584** and the control assembly **572** described above.

(214) Therefore, the charger **585** of the present invention can intelligently charge several battery packs step by step according to the priority level, so that the power levels of the several battery packs are matched with each other, so that the several battery packs cooperate to supply power to the device, which is convenient for the user to use the device in emergency. This effectively improves the user experience.

(215) The above description is only a preferred embodiment of the present invention and an explanation of the technical principles used. Those skilled in the art should understand that the scope of the invention involved in the present invention is not limited to a technical solution formed by a specific combination of the above technical features. At the same time, it should also

cover other technical solutions formed by arbitrarily combining the above technical features or their equivalent features without departing from the inventive concept. For example, the above features are similar to those disclosed in the present invention (but not limited to). The technical solution formed by replacing the technical features of the function with each other.

Claims

1. An electric vehicle, including: frame; a first power consuming unit and a second power consuming unit, the first power consuming unit and the second power consuming unit are connected to the frame; and a battery system includes a battery accommodating part connected to the frame, the battery accommodating part having a first power supply unit, a second power supply unit, a third power supply unit, and a fourth power supply unit, the first, second, third, and fourth power supply units being arranged separately on the battery accommodating part, the first power supply unit and the second power supply unit each include at least one battery pack, and the first power supply unit separately supplies power to the first power consuming unit, the second power supply unit separately supplies power to the second power consuming unit; wherein, the at least one battery pack can be removed from the first power supply unit or the second power supply unit and directly coupled to a hand-held tool to supply power thereto.
 2. The electric vehicle according to claim 1, wherein the number of the battery packs in the first power supply unit and the second power supply unit are the same or different.
 3. The electric vehicle according to claim 1, wherein the first power consuming unit and the second power consuming unit are detachably connected to the frame.
 4. The electric vehicle according to claim 1, further comprising a manipulation unit provided on the frame, and the manipulation unit is used to control the electric vehicle.
 5. The electric vehicle according to claim 4, wherein the control unit is electrically connected to the first power consuming unit and the second power consuming unit.
 6. The electric vehicle according to claim 4, wherein the manipulation unit further comprises a height adjustment unit, and the height adjustment unit is used to adjust the height of the electric vehicle.
-