

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12417808
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Lien; Yu-Chung et al.

Single-level cell programming with adaptive wordline ramp rate

Abstract

A processing device is operatively coupled to an array of memory cells. The processing device determines that a media endurance metric value for a string of the array of memory cells satisfies a first threshold criterion based on a first threshold value. The processing device further controls, based on the media endurance metric value, a ramp rate of a program pulse applied to a wordline of the string.

Inventors: Lien; Yu-Chung (San Jose, CA), Garrison; Joshua (Folsom, CA), Zhou; Zhenming (San Jose, CA)

Applicant: Micron Technology, Inc. (Boise, ID)

Family ID: 1000008818502

Assignee: Micron Technology, Inc. (Boise, ID)

Appl. No.: 18/496660

Filed: October 27, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240170071 A1	May. 23, 2024

Related U.S. Application Data

us-provisional-application US 63427151 20221122

Publication Classification

Int. Cl.: G11C13/00 (20060101); G11C16/08 (20060101); G11C16/10 (20060101); G11C16/34 (20060101)

U.S. Cl.:

CPC **G11C16/102** (20130101); **G11C16/08** (20130101); **G11C16/349** (20130101);

Field of Classification Search

CPC: G11C (13/0064)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2011/0214025	12/2010	Seko	714/720	G11C 13/0064

Primary Examiner: Lappas; Jason

Attorney, Agent or Firm: Lowenstein Sandler LLP

Background/Summary

RELATED APPLICATIONS (1) This application claims the benefit of U.S. Provisional Patent Application No. 63/427,151 filed Nov. 22, 2022, the entire contents of which are incorporated by reference herein.

TECHNICAL FIELD

(1) Embodiments of the disclosure relate generally to memory sub-systems, and more specifically, relate to single-level cell (SLC) programming with adaptive wordline ramp rate.

BACKGROUND

(2) A memory sub-system can include one or more memory devices that store data. The memory devices can be, for example, non-volatile memory devices and volatile memory devices. In general, a host system can utilize a memory sub-system to store data at the memory devices and to retrieve data from the memory devices.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) The present disclosure will be understood more fully from the detailed description given below and from the accompanying drawings of various embodiments of the disclosure.
- (2) FIG. 1A illustrates an example computing system that includes a memory sub-system in accordance with some embodiments of the present disclosure.
- (3) FIG. 1B is a block diagram of a memory device in communication with a memory sub-system controller of a memory sub-system, in accordance with some embodiments of the present disclosure.
- (4) FIG. 2 is a schematic of portions of an array of memory cells as could be used in a memory of the type described with reference to FIG. 1B in accordance with some embodiments of the present disclosure.
- (5) FIG. 3 is a graph illustrating performance when a ramp rate control of a program pulse is enabled or disabled for a wordline of a string of an array of memory cells in accordance with some

embodiments of the present disclosure.

(6) FIG. 4 is a graph of a program pulse with different ramps rates for a wordline of a string of an array of memory cells, in accordance with some embodiments of the present disclosure.

(7) FIG. 5 is a flow diagram of an example method of performing single-level cell (SLC) programming with an adaptive wordline ramp rate, in accordance with embodiments of the present disclosure.

(8) FIG. 6A is a flow diagram of an example method of performing memory cell programming with an adaptive wordline ramp rate, in accordance with embodiments of the present disclosure.

(9) FIG. 6B is a flow diagram of an example method of performing memory cell programming with an adaptive wordline ramp rate, in accordance with embodiments of the present disclosure.

(10) FIG. 7A is a graph of program pulses with different program voltage levels and ramps rates for a wordline of a string of an array of memory cells, in accordance with some embodiments of the present disclosure.

(11) FIG. 7B is a graph of voltage window expansion of a program pulse with different program voltage levels for a wordline of a string of an array of memory cells, in accordance with some embodiments of the present disclosure.

(12) FIG. 8 is a flow diagram of an example method of performing memory cell programming with different program voltage levels and ramps rates for a wordline of a string of an array of memory cells, in accordance with some embodiments of the present disclosure.

(13) FIG. 9 is a block diagram of an example computer system in which embodiments of the present disclosure can operate.

DETAILED DESCRIPTION

(14) Aspects of the present disclosure are directed to single-level cell (SLC) programming with adaptive wordline ramp rate. A memory sub-system can be a storage device, a memory module, or a hybrid of a storage device and memory module. Examples of storage devices and memory modules are described below in conjunction with FIGS. 1A-B. In general, a host system can utilize a memory sub-system that includes one or more components, such as memory devices that store data. The host system can provide data to be stored at the memory sub-system and can request data to be retrieved from the memory sub-system.

(15) A memory sub-system can include high density non-volatile memory devices where retention of data is desired when no power is supplied to the memory device. For example, NOT-AND (NAND) memory, such as 3D flash NAND memory, offers storage in the form of compact, high-density configurations. A non-volatile memory device is a package of one or more dice, each including one or more planes. For some types of non-volatile memory devices (e.g., NAND memory), each plane includes of a set of physical blocks. Each block includes of a set of pages. Each page includes of a set of memory cells (“cells”). A cell is an electronic circuit that stores information. Depending on the cell type, a cell can store one or more bits of binary information, and has various logic states that correlate to the number of bits being stored. The logic states can be represented by binary values, such as “0” and “1”, or combinations of such values.

(16) A memory device can include multiple memory cells arranged in a two-dimensional or a three-dimensional grid. The memory cells are formed onto a silicon wafer in an array of columns and rows. A wordline is a conductive line coupled to one or more rows of memory cells of a memory device. A bitline is a conductive line coupled to one or more columns of memory cells. The intersection of a bitline and wordline constitutes the address of the memory cell. A block refers to a unit of the memory device used to store data and can include a group of memory cells, a wordline group, a wordline, or individual memory cells. One or more blocks can be grouped together to form separate partitions (e.g., planes) of the memory device in order to allow concurrent operations to take place on each plane.

(17) During a program operation of a non-volatile memory device, a memory sub-system controller (e.g., processing device) directs the program operation in certain phases, including program and

program verify phases. For example, the controller causes a high program voltage pulse to be applied to a selected wordline of a block of the memory device during a program phase, followed by a program verify phase, during which the controller causes a verify voltage to be applied to the selected wordline. Alternatively, multiple program voltage pulses can be applied to the selected wordline of a block of the memory device during the program phase, followed by a program verify phase, in which the controller causes a verify voltage to be applied to the selected wordline.

(18) In certain memory devices, a memory configured as SLC memory may have two different trim settings during program operations. A static trim setting employs two program pulses and one program verify pulse, giving the SLC memory the advantage of higher endurance but has slower performance (e.g., time to program). The dynamic trim setting has one program pulse and one program verify pulse and gives the SLC memory better performance (e.g., time to program) but has less endurance, e.g., fewer program/erase cycles (PECs). The lack of endurance shortens the life of the SLC memory. Further, the lack of performance increases the length of the program operation, which can be especially impactful in high-priority and time-sensitive operations, such as SLC program operations.

(19) Aspects of the present disclosure address the above and other deficiencies by implementing SLC programming with an adaptive wordline ramp rate. In SLC programming with adaptive wordline ramp rate, the controller (e.g., a processing device) can program memory cells using different programming pulse ramp rates depending on a media endurance metric value. “Ramp rate” refers to the rate of change of the voltage level of a program pulse. For example, ramp rate may be depicted in graphical form, as shown in FIG. 4, as the slope of the leading edge of a program pulse **450**.

(20) In one embodiment, a processing device in a system is operatively coupled to an array of memory cells configured as SLC memory. In embodiments, the processing device determines that a media endurance metric value (e.g., a program/erase cycle (PEC) value, write amplification, or a combination thereof) for a subset of memory cells of the array of memory cells satisfies a threshold criterion (e.g., exceeds a certain threshold value). For example, the subset of memory cells may include a string (e.g., a series of connected memory cells in which the source of one cell is connected to the drain of the next one), a sub-block, or a physical block of memory cells. The PEC value and any additional write amplification (e.g., the write amplification caused by performing a refresh of data to rectify drifting threshold voltage levels) may be tracked from the time the memory device is put into operation. In some embodiments, the media endurance metric value satisfies the threshold criterion when the media endurance metric value is greater than or equal to a certain threshold value. For example, a threshold value may be determined based on statistical data collected in post-production testing, such that the determined threshold value would optimize chosen performance or endurance metric(s). The processing device may further control a ramp rate of a program pulse applied to a wordline addressing the subset of memory cells based on the media endurance value. In varied embodiments, the processing device can apply different granular levels of ramp rates to such wordlines depending on whether the media endurance value of the subset of memory cells meets corresponding granular levels of media endurance metric values, as will be discussed in more detail.

(21) In some embodiments, the processing device may further adjust, based on the media endurance value, the voltage of a program pulse applied to a wordline addressing the subset of memory cells. In varied embodiments, the processing device can apply, depending on whether the media endurance value of the subset of memory cells meets corresponding granular levels of threshold values, different granular levels of program voltage to such wordlines, as will be discussed in more detail.

(22) Advantages of this approach include, but are not limited to, improved SLC programming performance in the memory device. The SLC programming operation with an adaptive wordline ramp rate described herein allows for higher endurance in SLC memory devices and improved

performance (time to program) during programming operations at the memory devices. By achieving this performance-endurance balance, the present embodiments facilitate extending the life of SLC memory devices while maintaining high performance at the BOL and high reliability at the end of life (EOL) of the memory devices. Further, cycling degradation is alleviated for memory devices using the disclosed adaptive wordline ramp rate. For example, performance without significant cycling degradation can be achieved at higher media endurance metric values (e.g., PEC values) than can be when typical SLC programming is implemented.

(23) FIG. 1A illustrates an example computing system **100** that includes a memory sub-system **110** in accordance with some embodiments of the present disclosure. The memory sub-system **110** can include media, such as one or more volatile memory devices (e.g., memory device **140**), one or more non-volatile memory devices (e.g., memory device **130**), or a combination of such.

(24) A memory sub-system **110** can be a storage device, a memory module, or a hybrid of a storage device and memory module. Examples of a storage device include a solid-state drive (SSD), a flash drive, a universal serial bus (USB) flash drive, an embedded Multi-Media Controller (eMMC) drive, a Universal Flash Storage (UFS) drive, a secure digital (SD) card, and a hard disk drive (HDD). Examples of memory modules include a dual in-line memory module (DIMM), a small outline DIMM (SO-DIMM), and various types of non-volatile dual in-line memory modules (NVDIMMs).

(25) The computing system **100** can be a computing device such as a desktop computer, laptop computer, network server, mobile device, a vehicle (e.g., airplane, drone, train, automobile, or other conveyance), Internet of Things (IOT) enabled device, embedded computer (e.g., one included in a vehicle, industrial equipment, or a networked commercial device), or such computing device that includes memory and a processing device.

(26) The computing system **100** can include a host system **120** that is coupled to one or more memory sub-systems **110**. In some embodiments, the host system **120** is coupled to different types of memory sub-system **110**. FIG. 1A illustrates one example of a host system **120** coupled to one memory sub-system **110**. As used herein, “coupled to” or “coupled with” generally refers to a connection between components, which can be an indirect communicative connection or direct communicative connection (e.g., without intervening components), whether wired or wireless, including connections such as electrical, optical, magnetic, etc.

(27) The host system **120** can include a processor chipset and a software stack executed by the processor chipset. The processor chipset can include one or more cores, one or more caches, a memory controller (e.g., NVDIMM controller), and a storage protocol controller (e.g., PCIe controller, SATA controller). The host system **120** uses the memory sub-system **110**, for example, to write data to the memory sub-system **110** and read data from the memory sub-system **110**.

(28) The host system **120** can be coupled to the memory sub-system **110** via a physical host interface. Examples of a physical host interface include, but are not limited to, a serial advanced technology attachment (SATA) interface, a peripheral component interconnect express (PCIe) interface, universal serial bus (USB) interface, Fibre Channel, Serial Attached SCSI (SAS), a double data rate (DDR) memory bus, Small Computer System Interface (SCSI), a dual in-line memory module (DIMM) interface (e.g., DIMM socket interface that supports Double Data Rate (DDR)), etc. The physical host interface can be used to transmit data between the host system **120** and the memory sub-system **110**. The host system **120** can further utilize an NVM Express (NVMe) interface to access the memory components (e.g., memory devices **130**) when the memory sub-system **110** is coupled with the host system **120** by the PCIe interface. The physical host interface can provide an interface for passing control, address, data, and other signals between the memory sub-system **110** and the host system **120**. FIG. 1A illustrates a memory sub-system **110** as an example. In general, the host system **120** can access multiple memory sub-systems via a same communication connection, multiple separate communication connections, and/or a combination of communication connections.

(29) The memory devices **130**, **140** can include any combination of the different types of non-volatile memory devices and/or volatile memory devices. The volatile memory devices (e.g., memory device **140**) can be, but are not limited to, random access memory (RAM), such as dynamic random access memory (DRAM) and synchronous dynamic random access memory (SDRAM).

(30) Some examples of non-volatile memory devices (e.g., memory device **130**) include negative- and (NAND) type flash memory and write-in-place memory, such as three-dimensional cross-point (“3D cross-point”) memory. A cross-point array of non-volatile memory can perform bit storage based on a change of bulk resistance, in conjunction with a stackable cross-gridded data access array. Additionally, in contrast to many flash-based memories, cross-point non-volatile memory can perform a write in-place operation, where a non-volatile memory cell can be programmed without the non-volatile memory cell being previously erased. NAND type flash memory includes, for example, two-dimensional NAND (2D NAND) and three-dimensional NAND (3D NAND).

(31) Each of the memory devices **130** can include one or more arrays of memory cells. One type of memory cell, for example, single-level cells (SLC) can store one bit per cell. Other types of memory cells, such as multi-level cells (MLCs), triple level cells (TLCs), quad-level cells (QLCs) and penta-level (PLCs), can store multiple bits per cell. In some embodiments, each of the memory devices **130** can include one or more arrays of memory cells such as SLCs, MLCs, TLCs, QLCs, PLCs, or any combination of such. In some embodiments, a particular memory device can include an SLC portion, and an MLC portion, a TLC portion, a QLC portion or a PLC portion of memory cells. The memory cells of the memory devices **130** can be grouped as pages that can refer to a logical unit of the memory device used to store data. With some types of memory (e.g., NAND), pages can be grouped to form blocks.

(32) Although non-volatile memory components such as a 3D cross-point array of non-volatile memory cells and NAND type flash memory (e.g., 2D NAND, 3D NAND) are described, the memory device **130** can be based on any other type of non-volatile memory, such as read-only memory (ROM), phase change memory (PCM), self-selecting memory, other chalcogenide based memories, ferroelectric transistor random-access memory (FeTRAM), ferroelectric random access memory (FeRAM), magneto random access memory (MRAM), Spin Transfer Torque (STT)-MRAM, conductive bridging RAM (CBRAM), resistive random access memory (RRAM), oxide based RRAM (OxRAM), negative-or (NOR) flash memory, electrically erasable programmable read-only memory (EEPROM).

(33) A memory sub-system controller **115** (or controller **115** for simplicity) can communicate with the memory devices **130** to perform operations such as reading data, writing data, or erasing data at the memory devices **130** and other such operations. The memory sub-system controller **115** can include hardware such as one or more integrated circuits and/or discrete components, a buffer memory, or a combination thereof. The hardware can include a digital circuitry with dedicated (i.e., hard-coded) logic to perform the operations described herein. The memory sub-system controller **115** can be a microcontroller, special purpose logic circuitry (e.g., a field programmable gate array (FPGA), an application specific integrated circuit (ASIC), etc.), or other suitable processor.

(34) The memory sub-system controller **115** can include a processor **117** (e.g., a processing device) configured to execute instructions stored in a local memory **119**. In the illustrated example, the local memory **119** of the memory sub-system controller **115** includes an embedded memory configured to store instructions for performing various processes, operations, logic flows, and routines that control operation of the memory sub-system **110**, including handling communications between the memory sub-system **110** and the host system **120**.

(35) In some embodiments, the local memory **119** can include memory registers storing memory pointers, fetched data, etc. The local memory **119** can also include read-only memory (ROM) for storing micro-code. While the example memory sub-system **110** in FIG. 1A has been illustrated as including the memory sub-system controller **115**, in another embodiment of the present disclosure,

a memory sub-system **110** does not include a memory sub-system controller **115**, and can instead rely upon external control (e.g., provided by an external host, or by a processor or controller separate from the memory sub-system).

(36) In general, the memory sub-system controller **115** can receive commands or operations from the host system **120** and can convert the commands or operations into instructions or appropriate commands to achieve the desired access to the memory devices **130**. The memory sub-system controller **115** can be responsible for other operations such as wear leveling operations, garbage collection operations, error detection and error-correcting code (ECC) operations, encryption operations, caching operations, and address translations between a logical address (e.g., logical block address (LBA), namespace) and a physical address (e.g., physical block address) that are associated with the memory devices **130**. The memory sub-system controller **115** can further include host interface circuitry to communicate with the host system **120** via the physical host interface. The host interface circuitry can convert the commands received from the host system into command instructions to access the memory devices **130** as well as convert responses associated with the memory devices **130** into information for the host system **120**.

(37) The memory sub-system **110** can also include additional circuitry or components that are not illustrated. In some embodiments, the memory sub-system **110** can include a cache or buffer (e.g., DRAM) and address circuitry (e.g., a row decoder and a column decoder) that can receive an address from the memory sub-system controller **115** and decode the address to access the memory devices **130**.

(38) In some embodiments, the memory devices **130** include local media controllers **135** that operate in conjunction with memory sub-system controller **115** to execute operations on one or more memory cells of the memory devices **130**. An external controller (e.g., memory sub-system controller **115**) can externally manage the memory device **130** (e.g., perform media management operations on the memory device **130**). In some embodiments, a memory device **130** is a managed memory device, which is a raw memory device **130** having control logic (e.g., local controller **135**) on the die and a controller (e.g., memory sub-system controller **115**) for media management within the same memory device package. An example of a managed memory device is a managed NAND (MNAND) device. Memory device **130**, for example, can represent a single die having some control logic (e.g., local media controller **135**) embodied thereon. In some embodiments, one or more components of memory sub-system **110** can be omitted.

(39) In one embodiment, memory sub-system **110** includes a memory interface component **113**. Memory interface component **113** is responsible for handling interactions of memory sub-system controller **115** with the memory devices of memory sub-system **110**, such as memory device **130**. For example, memory interface component **113** can send memory access commands corresponding to requests received from host system **120** to memory device **130**, such as program commands, read commands, or other commands. In addition, memory interface component **113** can receive data from memory device **130**, such as data retrieved in response to a read command or a confirmation that a program command was successfully performed. In some embodiments, the memory sub-system controller **115** includes at least a portion of the memory interface **113**. For example, the memory sub-system controller **115** can include a processor **117** (e.g., a processing device) configured to execute instructions stored in local memory **119** for performing the operations described herein. In some embodiments, the memory interface component **113** is part of the host system **110**, an application, or an operating system. FIG. 1B is a simplified block diagram of a first apparatus, in the form of a memory device **130**, in communication with a second apparatus, in the form of a memory sub-system controller **115** of a memory sub-system (e.g., memory sub-system **110** of FIG. 1A), according to an embodiment. Some examples of electronic systems include personal computers, personal digital assistants (PDAs), digital cameras, digital media players, digital recorders, games, appliances, vehicles, wireless devices, mobile telephones and the like. The memory sub-system controller **115** (e.g., a controller external to the memory device **130**), may be a

memory controller or other external host device.

(40) Memory device **130** includes an array of memory cells **104** logically arranged in rows and columns. Memory cells of a logical row are typically connected to the same access line (e.g., a wordline) while memory cells of a logical column are typically selectively connected to the same data line (e.g., a bit line). A single access line may be associated with more than one logical row of memory cells and a single data line may be associated with more than one logical column. Memory cells (not shown in FIG. **1B**) of at least a portion of array of memory cells **104** are capable of being programmed to one of at least two target data states.

(41) Row decode circuitry **108** and column decode circuitry **109** are provided to decode address signals. Address signals are received and decoded to access the array of memory cells **104**. Memory device **130** also includes input/output (I/O) control circuitry **160** to manage input of commands, addresses and data to the memory device **130** as well as output of data and status information from the memory device **130**. An address register **114** is in communication with I/O control circuitry **160** and row decode circuitry **108** and column decode circuitry **109** to latch the address signals prior to decoding. A command register **124** is in communication with I/O control circuitry **160** and local media controller **135** to latch incoming commands.

(42) A controller (e.g., the local media controller **135** internal to the memory device **130**) controls access to the array of memory cells **104** in response to the commands and generates status information for the external memory sub-system controller **115**, i.e., the local media controller **135** is configured to perform access operations (e.g., read operations, programming operations and/or erase operations) on the array of memory cells **104**. The local media controller **135** is in communication with row decode circuitry **108** and column decode circuitry **109** to control the row decode circuitry **108** and column decode circuitry **109** in response to the addresses. In one embodiment, local media controller **135** can perform a double single-level cell (SLC) program operation to concurrently (i.e., at least partially overlapping in time) program memory cells in two or more separate sub-blocks of a block of memory array **104** using a single programming pulse.

(43) The local media controller **135** is also in communication with a cache register **172**. Cache register **172** latches data, either incoming or outgoing, as directed by the local media controller **135** to temporarily store data while the array of memory cells **104** is busy writing or reading, respectively, other data. During a program operation (e.g., write operation), data may be passed from the cache register **172** to the data register **170** for transfer to the array of memory cells **104**; then new data may be latched in the cache register **172** from the I/O control circuitry **160**. During a read operation, data may be passed from the cache register **172** to the I/O control circuitry **160** for output to the memory sub-system controller **115**; then new data may be passed from the data register **170** to the cache register **172**. The cache register **172** and/or the data register **170** may form (e.g., may form a portion of) a page buffer of the memory device **130**. A page buffer may further include sensing devices (not shown in FIG. **1B**) to sense a data state of a memory cell of the array of memory cells **104**, e.g., by sensing a state of a data line connected to that memory cell. A status register **122** may be in communication with I/O control circuitry **160** and the local memory controller **135** to latch the status information for output to the memory sub-system controller **115**.

(44) Memory device **130** receives control signals at the memory sub-system controller **115** from the local media controller **135** over a control link **132**. For example, the control signals can include a chip enable signal CE #, a command latch enable signal CLE, an address latch enable signal ALE, a write enable signal WE #, a read enable signal RE #, and a write protect signal WP #. Additional or alternative control signals (not shown) may be further received over control link **132** depending upon the nature of the memory device **130**. In one embodiment, memory device **130** receives command signals (which represent commands), address signals (which represent addresses), and data signals (which represent data) from the memory sub-system controller **115** over a multiplexed input/output (I/O) bus **134** and outputs data to the memory sub-system controller **115** over I/O bus **134**.

(45) For example, the commands may be received over input/output (I/O) pins [7:0] of I/O bus **134** at I/O control circuitry **160** and may then be written into command register **124**. The addresses may be received over input/output (I/O) pins [7:0] of I/O bus **134** at I/O control circuitry **160** and may then be written into address register **114**. The data may be received over input/output (I/O) pins [7:0] for an 8-bit device or input/output (I/O) pins [15:0] for a 16-bit device at I/O control circuitry **160** and then may be written into cache register **172**. The data may be subsequently written into data register **170** for programming the array of memory cells **104**.

(46) In an embodiment, cache register **172** may be omitted, and the data may be written directly into data register **170**. Data may also be output over input/output (I/O) pins [7:0] for an 8-bit device or input/output (I/O) pins [15:0] for a 16-bit device. Although reference may be made to I/O pins, they may include any conductive node providing for electrical connection to the memory device **130** by an external device (e.g., the memory sub-system controller **115**), such as conductive pads or conductive bumps as are commonly used.

(47) It will be appreciated by those skilled in the art that additional circuitry and signals can be provided, and that the memory device **130** of FIG. **1B** has been simplified. It should be recognized that the functionality of the various block components described with reference to FIG. **1B** may not necessarily be segregated to distinct components or component portions of an integrated circuit device. For example, a single component or component portion of an integrated circuit device could be adapted to perform the functionality of more than one block component of FIG. **1B**. Alternatively, one or more components or component portions of an integrated circuit device could be combined to perform the functionality of a single block component of FIG. **1B**. Additionally, while specific I/O pins are described in accordance with popular conventions for receipt and output of the various signals, it is noted that other combinations or numbers of I/O pins (or other I/O node structures) may be used in the various embodiments.

(48) FIG. **2** is a schematic of portions of an array of memory cells **104**, such as a NAND memory array, as could be used in a memory of the type described with reference to FIG. **1B** according to an embodiment. Memory array **104** includes access lines, such as wordlines **202.sub.0** to **202.sub.N**, and data lines, such as bit lines **204.sub.0** to **204.sub.M**. The wordlines **202** can be connected to global access lines (e.g., global wordlines), not shown in FIG. **2**, in a many-to-one relationship. For some embodiments, memory array **104** can be formed over a semiconductor that, for example, can be conductively doped to have a conductivity type, such as a p-type conductivity, e.g., to form a p-well, or an n-type conductivity, e.g., to form an n-well.

(49) Memory array **104** can be arranged in rows (each corresponding to a wordline **202**) and columns (each corresponding to a bit line **204**). Each column can include a string of series-connected memory cells (e.g., non-volatile memory cells), such as one of NAND strings **206.sub.0** to **206.sub.M**. Each NAND string **206** can be connected (e.g., selectively connected) to a common source (SRC) **216** and can include memory cells **208.sub.0** to **208.sub.N**. The memory cells **208** can represent non-volatile memory cells for storage of data. The memory cells **208** of each NAND string **206** can be connected in series between a select gate **210** (e.g., a field-effect transistor), such as one of the select gates **210.sub.0** to **210.sub.M** (e.g., that can be source select transistors, commonly referred to as select gate source), and a select gate **212** (e.g., a field-effect transistor), such as one of the select gates **212.sub.0** to **212.sub.M** (e.g., that can be drain select transistors, commonly referred to as select gate drain). Select gates **210.sub.0** to **210.sub.M** can be commonly connected to a select line **214**, such as a source select line (SGS), and select gates **212.sub.0** to **212.sub.M** can be commonly connected to a select line **215**, such as a drain select line (SGD). Although depicted as traditional field-effect transistors, the select gates **210** and **212** can utilize a structure similar to (e.g., the same as) the memory cells **208** (e.g., metal-oxide-semiconductor field-effect transistor (MOSFET) structures such as silicon-oxide-nitride-oxide-silicon (SONOS) MOSFET structure). The select gates **210** and **212** can represent a number of select gates connected in series, with each select gate in series configured to receive a same or independent control signal.

(50) A source of each select gate **210** can be connected to common source **216**. The drain of each select gate **210** can be connected to a memory cell **208.sub.0** of the corresponding NAND string **206**. For example, the drain of select gate **210.sub.0** can be connected to memory cell **208.sub.0** of the corresponding NAND string **206.sub.0**. Therefore, each select gate **210** can be configured to selectively connect a corresponding NAND string **206** to the common source **216**. A control gate of each select gate **210** can be connected to the select line **214**.

(51) The drain of each select gate **212** can be connected to the bit line **204** for the corresponding NAND string **206**. For example, the drain of select gate **212.sub.0** can be connected to the bit line **204.sub.0** for the corresponding NAND string **206.sub.0**. The source of each select gate **212** can be connected to a memory cell **208.sub.N** of the corresponding NAND string **206**. For example, the source of select gate **212.sub.0** can be connected to memory cell **208.sub.N** of the corresponding NAND string **206.sub.0**. Therefore, each select gate **212** can be configured to selectively connect a corresponding NAND string **206** to the corresponding bit line **204**. A control gate of each select gate **212** can be connected to select line **215**.

(52) The memory array **104** in FIG. 2 can be a quasi-two-dimensional memory array and can have a generally planar structure, e.g., where the common source **216**, NAND strings **206** and bit lines **204** extend in substantially parallel planes. Alternatively, the memory array **104** in FIG. 2 can be a three-dimensional memory array, e.g., where NAND strings **206** can extend substantially perpendicular to a plane containing the common source **216** and to a plane containing the bit lines **204** that can be substantially parallel to the plane containing the common source **216**.

(53) Typical construction of memory cells **208** includes a data-storage structure **234** (e.g., a floating gate, charge trap, and the like) that can determine a data state of the memory cell (e.g., through changes in threshold voltage), and a control gate **236**, as shown in FIG. 2. The data-storage structure **234** can include both conductive and dielectric structures while the control gate **236** is generally formed of one or more conductive materials. In some cases, memory cells **208** can further have a defined source/drain (e.g., source) **230** and a defined source/drain (e.g., drain) **232**. The memory cells **208** have their control gates **236** connected to (and in some cases form) a wordline **202**.

(54) A column of the memory cells **208** can be a NAND string **206** or a number of NAND strings **206** selectively connected to a given bit line **204**. A row of the memory cells **208** can be memory cells **208** commonly connected to a given wordline **202**. A row of memory cells **208** can, but need not, include all the memory cells **208** commonly connected to a given wordline **202**. Rows of the memory cells **208** can often be divided into one or more groups of physical pages of memory cells **208**, and physical pages of the memory cells **208** often include every other memory cell **208** commonly connected to a given wordline **202**. For example, the memory cells **208** commonly connected to wordline **202.sub.N** and selectively connected to even bit lines **204** (e.g., bit lines **204.sub.0**, **204.sub.2**, **204.sub.4**, etc.) can be one physical page of the memory cells **208** (e.g., even memory cells) while memory cells **208** commonly connected to wordline **202.sub.N** and selectively connected to odd bit lines **204** (e.g., bit lines **204.sub.1**, **204.sub.3**, **204.sub.5**, etc.) can be another physical page of the memory cells **208** (e.g., odd memory cells).

(55) Although bit lines **204.sub.3-204.sub.5** are not explicitly depicted in FIG. 2, it is apparent from the figure that the bit lines **204** of the array of memory cells **104** can be numbered consecutively from bit line **204.sub.0** to bit line **204.sub.M**. Other groupings of the memory cells **208** commonly connected to a given wordline **202** can also define a physical page of memory cells **208**. For certain memory devices, all memory cells commonly connected to a given wordline can be deemed a physical page of memory cells. The portion of a physical page of memory cells (which, in some embodiments, could still be the entire row) that is read during a single read operation or programmed during a single programming operation (e.g., an upper or lower page of memory cells) can be deemed a logical page of memory cells. A block of memory cells can include those memory cells that are configured to be erased together, such as all memory cells connected to wordlines

202.sub.0-202.sub.N (e.g., all NAND strings **206** sharing common wordlines **202**). Unless expressly distinguished, a reference to a page of memory cells herein refers to the memory cells of a logical page of memory cells. Although the example of FIG. 2 is discussed in conjunction with NAND flash, the embodiments and concepts described herein are not limited to a particular array architecture or structure, and can include other structures (e.g., SONOS, phase change, ferroelectric, etc.) and other architectures (e.g., AND arrays, NOR arrays, etc.).

(56) In one embodiment, memory device **130** includes local media controller **135** and a memory array **104**. As described herein, local media controller **135** can perform a program operation on the memory cells (e.g., memory cells **208.sub.0** to **202.sub.M**) of memory array **104**. The program operation through bitline(s) **204.sub.0** to **204.sub.M** can be applied to any direction of program sequence along strings **206.sub.0** to **206.sub.M** or sub-blocks of memory cells (e.g., source to drain (S2D) or drain to source (D2S)). For example, in some embodiments, the program operation may be applied from source **230** to drain **232** or in the opposite direction (e.g., drain **232** to source **230**). In further embodiments, the program operation may be applied from common source **216** to the drain of select gates(s) **212.sub.0** to **212.sub.M** or in the opposite direction from the drain of select gates(s) **212.sub.0** to **212.sub.M** to common source **216**. A program operation can include, for example, a program phase and a program verify phase. During the program phase, a program voltage is applied to selected wordline(s) **202.sub.0** to **202.sub.N** of the memory array **104**, in order to program certain level(s) of charge to selected memory cells coupled to wordline(s) **202.sub.0** to **202.sub.N** representative of a desired value(s). In one embodiment, by conditioning the channel potential associated with multiple sub-blocks according to a data pattern to be programmed to the memory cells contained therein before the program voltage is applied to one or more selected wordline(s) **202.sub.0** to **202.sub.N**, multiple memory cells in separate sub-blocks can be accurately programmed using a single programming pulse.

(57) For example, at the start of the program operation, local media controller **135** may cause a pass voltage to be applied to multiple wordlines (e.g., wordline(s) **202.sub.0** to **202.sub.N**) of a block of memory array **104** in memory device **130**. The block can include multiple sub-blocks, and the pass voltage can boost a channel potential of each of the multiple sub-blocks to a boost voltage (Vboost). Local media controller **135** can further selectively discharge the boost voltage from one or more of the multiple sub-blocks according to a data pattern representing a sequence of bits to be programmed to respective memory cells (e.g., memory cells **208.sub.0** to **202.sub.M**) of those sub-blocks. This selective discharge can result in the channel potential of the sub-blocks containing memory cells to be programmed to discharge to a ground voltage. In addition, local media controller **135** may cause a single programming pulse to be applied to a selected wordline of the multiple wordlines **202.sub.0** to **202.sub.N** of the block to program the respective memory cells of the multiple sub-blocks according to the data pattern. In one embodiment, the memory cells in those sub-blocks for which the channel potential was discharged to ground will be programmed, while memory cells in those sub-blocks for which the channel potential was not discharged and remained at the boost voltage will be inhibited and not programmed. A program verify phase can then be initiated to verify that the memory cells were programmed correctly according to the data pattern.

(58) FIG. 3 is a graph illustrating performance (e.g., time to program (Tprog)) when a ramp rate control of a program pulse is in an enabled state **320** or a disabled state **310** for a wordline of a string of an array of memory cells, in accordance with some embodiments of the present disclosure. In some embodiments, the array of memory cells may be configured as SLC memory. In some embodiments, the ramp rate control disabled state **310** may correlate to no ramp rate control, a default ramp rate **410** described in FIG. 4, or to any ramp rate used at the BOL of a memory device. In some embodiments, the ramp rate control enabled state **320** may correlate to controlling the ramp rate, e.g., by controlling the ramp rate to be any of a first ramp rate **420**, a second ramp rate **430**, a third ramp rate **440**, as illustrated in FIG. 4, or another controlled ramp rate not specifically

illustrated.

(59) In some embodiments, the controller **115** may enable or disable a ramp rate control, in response to a media endurance metric value satisfying a threshold criterion. In some embodiments, a threshold criterion may be a logical condition (e.g., a PEC value must be greater than or equal to a certain number of PECs (e.g., a PEC threshold value) for the threshold criterion to be satisfied). For example, a threshold value may be equal to a fixed number of PECs or another media endurance metric (e.g., a threshold value may be determined based on statistical data collected in post-production testing, such that the determined threshold value would optimize chosen performance or endurance metric(s)). In some embodiments, for example, the EOL for an SLC memory cell may be associated with a certain number of PECs. For example, the first threshold value may be a certain percentage of the EOL PECs. In some embodiments, threshold values may be determined by selecting threshold values, switching the WL ramp rate at each threshold value, checking the reliability at EOL PEC, and adjusting the threshold values according to a desired reliability profile. In some embodiments a ramp rate control may be enabled when, for example, a block reaches a number of PECs that is greater than or equal to a threshold criterion.

(60) FIG. **4** is a graph of a program pulse **450** with different ramps rates for a wordline of a string of an array of memory cells, in accordance with some embodiments of the present disclosure. In some embodiments, the array of memory cells may be configured as SLC memory. “Ramp rate” refers to the rate of change of the voltage level of a program pulse. Ramp rate may be depicted in graphical form, as shown in FIG. **4**, as the slope of the leading edge of a program pulse **450**. Accordingly, a steeper slope corresponds to a greater ramping rate. The slope of a curve at a point on that curve may be determined by calculating the slope of the line tangent to the curve at that point. The average slope of a portion of a curve may be determined by calculating the slope between the two end points of that portion of the curve. In some embodiments, the ramp speed of a default ramp rate **410** is greater than a first ramp rate **420**, the first ramp rate **420** is greater than a second ramp rate **430**, and the second ramp rate **430** is greater than a third ramp rate **440**. In some embodiments, the default ramp rate **410** can be the fastest ramp rate used at the beginning of life (BOL) of a memory device.

(61) In some embodiments, the controller **115** may set the ramp rate of programming voltage pulses applied to a block to the default ramp rate if the media endurance metric value of the block does not satisfy a threshold criterion. In these embodiments, the threshold criterion may be based on a threshold value (e.g., a fixed PEC value, write amplification, and/or the like). For example, a threshold value may be equal to a fixed number of PECs or another media endurance metric (e.g., a threshold value may be determined based on statistical data collected in post-production testing, such that the determined threshold value would optimize chosen performance or endurance metric(s)). In these and other embodiments, a threshold criterion is satisfied if the media endurance metric value is greater than (or greater than or equal to) the threshold value. In these and other embodiments, a threshold criterion is not satisfied when the media endurance metric value is less than the threshold value. In some embodiments, the threshold value and media endurance metric value may include an indication of a relative value between the two values (e.g., the media endurance metric value being less than the threshold value by a percentage).

(62) In some embodiments, the controller **115** may cause the wordline ramp rate to be set to the first ramp rate **420** when the media endurance metric value of the block satisfies the first threshold criterion. “Ramp rate” refers to the rate of change of the voltage level of a program pulse. In some embodiments, controlling of the wordline ramp rate may be done in stages (e.g., multiple threshold criteria correlating to multiple ramp rates of different levels of granularity). In some embodiments, ramp rate may be determined or affected by trim parameters in a NAND component such as `T_tz_step_wait` and `tz_step`. `T_tz_step_wait` may control the length of time for each `tz_step` (amplitude of step). In some embodiments, adjusting these parameters may control the slope of the ramp rate. In some embodiments, a ramp rate may be determined based on statistical data collected

in post-production testing, such that the determined ramp rate would optimize chosen performance or endurance metric(s).

(63) FIG. 5 is a flow diagram of an example method **500** of performing SLC programming with an adaptive wordline ramp rate, in accordance with embodiments of the present disclosure. The method **500** can be performed by processing logic that can include hardware (e.g., processing device, circuitry, dedicated logic, programmable logic, microcode, hardware of a device, integrated circuit, etc.), software (e.g., instructions run or executed on a processing device), or a combination thereof. In some embodiments, the method **500** is performed by the local media controller **135** of FIGS. **1A-1B**. Although shown in a particular sequence or order, unless otherwise specified, the order of the processes can be modified. Thus, the illustrated embodiments should be understood only as examples, and the illustrated processes can be performed in a different order, and some processes can be performed in parallel. Additionally, one or more processes can be omitted in various embodiments. Thus, not all processes are required in every embodiment. Other process flows are possible.

(64) In some embodiments, at operation **510** an SLC program command may be given by the memory subsystem controller **115**.

(65) At operation **520**, the processing logic determines that a media endurance metric value (e.g., PEC value) satisfies a threshold criterion. Alternatively, the processing logic may determine that the media endurance metric value does not satisfy the threshold criterion and, in response to determining that the media endurance metric value does not satisfy the threshold criterion, the method continues to the SLC program operation **540**. In some embodiments, the threshold criterion may be a media endurance metric threshold value such as a PEC threshold value, write amplification, or a combination thereof.

(66) At operation **530**, the processing logic, in response to the determining, enables a controlled wordline ramp rate (e.g., ramp rate control enabled state **320**).

(67) At operation **540**, the processing logic executes the SLC program command and completes a corresponding SLC program operation.

(68) FIG. **6A** is a flow diagram of an example method **600** of performing memory cell programming with an adaptive wordline ramp rate, in accordance with embodiments of the present disclosure. The method **600** can be performed by processing logic that can include hardware (e.g., processing device, circuitry, dedicated logic, programmable logic, microcode, hardware of a device, integrated circuit, etc.), software (e.g., instructions run or executed on a processing device), or a combination thereof. In some embodiments, the method **600** is performed by the local media controller **135** of FIGS. **1A-1B**. Although shown in a particular sequence or order, unless otherwise specified, the order of the processes can be modified. Thus, the illustrated embodiments should be understood only as examples, and the illustrated processes can be performed in a different order, and some processes can be performed in parallel. Additionally, one or more processes can be omitted in various embodiments. Thus, not all processes are required in every embodiment. Other process flows are possible.

(69) At operation **610** a processing device accesses an array of memory cells. This array of memory cells may be the array of memory cells **104** discussed with reference to FIGS. **1A-1B**. In some embodiments, the array of memory cells may be configured as SLC memory.

(70) At operation **620**, the processing logic determines that a media endurance metric value for a string of the array of memory cells satisfies a first threshold criterion based on a first threshold value. In some embodiments, the processing logic tracks the media endurance metric value over time as a PEC value, write amplification, or a combination thereof.

(71) At operation **630**, the processing logic controls a ramp rate of a program pulse applied to a wordline of the string based on the media endurance metric value. In some embodiments, the processing logic determines that the media metric value does not satisfy the first threshold criterion and in response to determining that the media metric value does not satisfy the first threshold

criterion, the processing logic sets the ramp rate to a default ramp rate (e.g., default ramp rate **410**). In some embodiments, the controlling may comprise setting the ramp rate according to a difference between the threshold value (e.g., the first threshold value) and the media endurance metric value.

(72) FIG. **6B** is a flow diagram of an example method **650** of performing memory cell programming with an adaptive wordline ramp rate, in accordance with embodiments of the present disclosure. The method **650** can be performed by processing logic that can include hardware (e.g., processing device, circuitry, dedicated logic, programmable logic, microcode, hardware of a device, integrated circuit, etc.), software (e.g., instructions run or executed on a processing device), or a combination thereof. In some embodiments, the method **650** is performed by the local media controller **135** of FIGS. **1A-1B**. Although shown in a particular sequence or order, unless otherwise specified, the order of the processes can be modified. Thus, the illustrated embodiments should be understood only as examples, and the illustrated processes can be performed in a different order, and some processes can be performed in parallel. Additionally, one or more processes can be omitted in various embodiments. Thus, not all processes are required in every embodiment. Other process flows are possible.

(73) At operation **655** a processing device accesses an array of memory cells. This array of memory cells may be the array of memory cells discussed with reference to FIGS. **1A-1B**. In some embodiments, the array of memory cells may be configured as SLC memory.

(74) At operation **660** the processing logic determines that a media endurance metric value (e.g., PEC value) for a string of the array of memory cells satisfies a first threshold criterion based on a first threshold value.

(75) At operation **665**, the processing logic controls a ramp rate of a program pulse applied to a wordline of the string based on the media endurance metric value.

(76) At operation **670**, in response to the determining that the media endurance metric value of the string satisfies the first threshold criterion but not a second threshold criterion based on a second threshold value that is greater than the first threshold value, the processing logic causes the ramp rate to be set to a first ramp rate (e.g., first ramp rate **420**).

(77) At operation **675**, in response to determining that the media endurance metric value of the string satisfies the second threshold criterion but not a third threshold criterion based on a third threshold value that is greater than the second threshold value, the processing logic causes the ramp rate to be set to a second ramp rate (e.g., second ramp rate **430**) that is lower than the first ramp rate.

(78) At operation **680**, in response to determining that the media endurance metric value of the string satisfies the third threshold criterion, the processing logic causes the ramp rate to be set to a third ramp rate (third ramp rate **440**) that is lower than the second ramp rate.

(79) In some embodiments, the threshold criteria may comprise more than the first threshold criterion, the second threshold criterion, and the third threshold criterion. For example, there may be a fourth threshold criterion, a fifth threshold criterion, and a sixth threshold criterion, or any number of threshold criteria. In some embodiments, the threshold values may comprise more than the first threshold value, the second threshold value, and the third threshold value. For example, there may be a fourth threshold value, a fifth threshold value, and a sixth threshold value, or any number of threshold values. In further embodiments, the ramp rates may include more than the default ramp rate **410**, the first ramp rate **420**, the second ramp rate **430**, and the third ramp rate **440**. For example, there may be a fourth ramp rate, a fifth ramp rate, and a sixth ramp rate, or any number of ramp rates. In some embodiments, these further threshold criteria, threshold values, and ramp rates may correspond to each other, and the ramp rate may be controlled based on a determining that the media endurance metric value of the string satisfies one of the threshold criteria.

(80) In some embodiments, the threshold values may be determined based on statistical data collected in post-production testing, such that the determined threshold values would optimize

chosen performance or endurance metric(s).

(81) In some embodiments, a multi-stage control of wordline ramp rates may be implemented. One embodiment is described in Table 1 below. Referring to Table 1, threshold value 1 is less than threshold value 2; threshold value 2 is less than threshold value 3; and threshold value 3 is less than threshold value 4. In some embodiments, threshold criterion 1 is based on threshold value 1, threshold criterion 2 is based on threshold value 2, threshold criterion 3 is based on threshold value 3, and threshold criterion 4 is based on threshold value 4. In further reference to Table 1, default ramp rate **410** is higher than first ramp rate **420**; first ramp rate **420** is higher than second ramp rate **430**; and second ramp rate **430** is higher than third ramp rate **440**.

(82) TABLE-US-00001 TABLE 1 Media Endurance Metric Value Wordline Ramp Rate Media Endurance Metric Value $\leq$ Threshold Criterion 1 Threshold Value 1 is not satisfied Default Ramp Rate 410 Threshold Value 1 $\leq$ Media Endurance Threshold Criterion 1 Metric Value $\leq$ Threshold Value 2 is satisfied First Ramp Rate 420 Threshold Value 2 $\leq$ Media Endurance Threshold Criterion 2 Metric Value $\leq$ Threshold Value 3 is satisfied Second Ramp Rate 430 Threshold Value 3 $\leq$ Media Endurance Threshold Criterion 3 Metric Value $\leq$ Threshold Value 4 is satisfied Third Ramp Rate 440

(83) In some embodiments, to satisfy a threshold criterion a media endurance metric value may be greater than or equal to the threshold value that the threshold criterion is based on. In some embodiments, to satisfy the threshold criterion the media endurance metric value may be greater than the threshold value that the threshold criterion is based on.

(84) FIG. 7A is a graph of program pulses with different program voltage levels (e.g., voltage amplitudes of the program pulse) and ramps rates for a wordline of a string of an array of memory cells, in accordance with some embodiments of the present disclosure. In some embodiments, the array of memory cells may be configured as SLC memory. Ramp rate may be depicted in graphical form, as shown in FIG. 7A, as the slope of the leading edge of a program pulse **450**. Accordingly, a steeper slope corresponds to a greater ramping rate. The slope of a curve at a point on the curve may be determined by calculating the slope of the line tangent to the curve at that point. The average slope of a portion of a curve may be determined by calculating the slope between the two end points of that portion of the curve. In some embodiments, the ramp speed of the default ramp rate **410** is greater than the ramp speed of the first ramp rate **420**, and the ramp speed of the first ramp rate **420** is greater than the ramp speed of the second ramp rate **430**. In some embodiments, the default ramp rate **410** is the fastest ramp rate (greatest ramp speed) used at the BOL of a memory device.

(85) In some embodiments, the controller **115** may set the voltage of a program pulse to a default program voltage level when the media endurance metric value of the block does not satisfy a threshold criterion. In these embodiments, the threshold criterion may be a fixed PEC value, write amplification, and/or the like. In some embodiments, the program voltage is the maximum voltage level of the program pulse and is referred to herein as the voltage of the program pulse. In some embodiments, a default program voltage level **710** is less than a first program voltage level **720**, and first program voltage level **720** is less than a second program voltage level **730**. In some embodiments default program voltage level **710** is the lowest program voltage level used at the BOL of a memory device.

(86) In some embodiments, the threshold criteria may comprise more than the first threshold criterion, the second threshold criterion, and the third threshold criterion. For example, there may be a fourth threshold criterion, a fifth threshold criterion, and a sixth threshold criterion, or any number of threshold criteria. In some embodiments, the threshold values may comprise more than the first threshold value, the second threshold value, and the third threshold value. For example, there may be a fourth threshold value, a fifth threshold value, and a sixth threshold value, or any number of threshold values. In some embodiments, the ramp rates may comprise more than the default ramp rate **410**, the first ramp rate **420**, and the second ramp rate **430**. Further embodiments

may include, for example, a third ramp rate, a fourth ramp rate, or any number of ramp rates. In some embodiments, the program voltage levels may comprise more than the default program voltage level **710**, the first program voltage level **720**, and the second program voltage level **730**. Further embodiments may include, for example, a third program voltage level, a fourth program voltage level, a fifth program voltage level, or any number of program voltage levels. In some embodiments, these further threshold criteria, threshold values, ramps rates, and program voltage levels may correspond to each other, and the program voltage level may be controlled based on a determining that the media endurance metric value of the string satisfies at least one of the threshold criteria.

(87) In some embodiments, the threshold values may be determined based on statistical data collected in post-production testing, such that the determined threshold values would optimize chosen performance or endurance metric(s). In some embodiments, a voltage level may be determined based on statistical data collected in post-production testing, such that the determined voltage level would optimize chosen performance or endurance metric(s). In some embodiments, for example, there may be a target voltage level for an SLC program state. In some embodiments, measurements may be taken under different PEC values to determine if the voltage level is sufficient to achieve a target voltage distribution.

(88) FIG. 7B is a graph of voltage window expansion of a program pulse with different program voltage levels (e.g., voltages of the program pulse) for a wordline of a string of an array of memory cells, in accordance with some embodiments of the present disclosure. In some embodiments, the array of memory cells may be configured as SLC memory. In some embodiments, a voltage window (e.g., BOL voltage window **765**) is broadened at the EOL **770** of a memory device. For example, a BOL voltage window **765** may be less than an EOL voltage window **775**. In one embodiment, at the BOL **760** of a memory device the voltage of the program pulse is low (e.g., program voltage **780** is low), and the ramp rate is high. Then, at the EOL **770** of the memory device, the voltage of the program pulse (e.g., program voltage **780**) increases (e.g., BOL voltage window **765** expands to EOL voltage window **775**), and the ramp rate decreases.

(89) FIG. 8 is a flow diagram of an example method **800** of performing memory cell programming with different program voltage levels (e.g., voltages of the program pulse) and ramps rates for a wordline of a string of an array of memory cells, in accordance with some embodiments of the present disclosure. The method **800** can be performed by processing logic that can include hardware (e.g., processing device, circuitry, dedicated logic, programmable logic, microcode, hardware of a device, integrated circuit, etc.), software (e.g., instructions run or executed on a processing device), or a combination thereof. In some embodiments, the method **800** is performed by the local media controller **135** of FIGS. 1A-1B. Although shown in a particular sequence or order, unless otherwise specified, the order of the processes can be modified. Thus, the illustrated embodiments should be understood only as examples, and the illustrated processes can be performed in a different order, and some processes can be performed in parallel. Additionally, one or more processes can be omitted in various embodiments. Thus, not all processes are required in every embodiment. Other process flows are possible.

(90) At operation **810**, a processing logic accesses an array of memory cells. This array of memory cells may be the array of memory cells discussed with reference to FIGS. 1A-1B. In some embodiments, the array of memory cells may be configured as SLC memory.

(91) At operation **820**, the processing logic determines that a media endurance metric value (e.g., PEC value) for a string of the array of memory cells satisfies a first threshold criterion based on a first threshold value.

(92) At operation **830**, the processing logic controls a ramp rate of a program pulse applied to a wordline of the string based on the media endurance metric value.

(93) At operation **840**, the processing logic adjusts a voltage of a program pulse applied to the wordline of the string based on the media endurance metric value.

- (94) At operation **850**, in response to the determining that the media endurance metric value of the string satisfies the first threshold criterion but not a second threshold criterion based on a second threshold value that is greater than the first threshold value, the processing logic causes the voltage of the program pulse (e.g., program voltage level) to be set to a first program voltage level (e.g., first program voltage level **720**).
- (95) At operation **860**, in response to determining that the media endurance metric value (e.g., PEC value) of the string satisfies the second threshold criterion but not a third threshold criterion based on a third threshold value that is greater than the second threshold value, the processing logic causes the voltage of the program pulse (e.g., program voltage level) to be set to a second program voltage level (e.g., second program voltage level **730**) that is higher than the first program voltage level.
- (96) At operation **870**, in response to determining that the media endurance metric value of the string satisfies the third threshold criterion, the processing logic causes the voltage of the program pulse (e.g., program voltage level) to be set to a third program voltage level (not shown in FIG. 7A) that is higher than the second program voltage level. In some embodiments, the increasing of the voltage of the program pulse (e.g., program voltage) may be according to a difference between the threshold value (e.g., the first threshold value) and the media endurance metric value (e.g., PEC value).
- (97) In some embodiments, the threshold criteria may comprise more than the first threshold criterion, the second threshold criterion, and the third threshold criterion. For example, there may be a fourth threshold criterion, a fifth threshold criterion, and a sixth threshold criterion, or any number of threshold criteria. In some embodiments, the threshold values may comprise more than the first threshold value, the second threshold value, and the third threshold value. For example, there may be a fourth threshold value, a fifth threshold value, and a sixth threshold value, or any number of threshold values. In some embodiments, the ramp rates may comprise more than the default ramp rate **410**, the first ramp rate **420**, and the second ramp rate **430**. Further embodiments may include, for example, a third ramp rate **440**, a fourth ramp rate, or any number of ramp rates. In some embodiments, the program voltage levels (e.g., voltage levels of the program pulse) may comprise more than the default program voltage level **710**, the first program voltage level **720**, and the second program voltage level **730**. Further embodiments may include, for example, a third program voltage level, a fourth program voltage level, a fifth program voltage level, or any number of program voltage levels. In some embodiments, these further threshold criteria, threshold values, ramp rates, and program voltage levels may correspond to each other, and the program voltage level may be controlled based on a determining that the media endurance metric value (e.g., PEC value) of the string satisfies one of the threshold criteria.
- (98) In some embodiments, the threshold values may be determined based on statistical data collected in post-production testing, such that the determined threshold values would optimize chosen performance or endurance metric(s).
- (99) In some embodiments, a multi-stage control of program voltage level may be implemented. One embodiment is described in Table 2 below. Referring to Table 2, threshold value 1 is less than threshold value 2; threshold value 2 is less than threshold value 3; and threshold value 3 is less than threshold value 4. In some embodiments, threshold criterion 1 is based on threshold value 1, threshold criterion 2 is based on threshold value 2, threshold criterion 3 is based on threshold value 3, and threshold criterion 4 is based on threshold value 4. In further reference to Table 2, default program voltage level **710** is lower than first program voltage level **720**; first program voltage level **720** is lower than second program voltage level **730**; and second program voltage level **730** is lower than the third program voltage level (not shown in FIG. 7A).
- (100) TABLE-US-00002 TABLE 2 Program Voltage Level (e.g., voltage of Media Endurance Metric Value the program pulse) Media Endurance Metric Value $\leq$ Threshold Criterion 1 is not Threshold Value 1 satisfied Default Program Voltage Level 710 Threshold Value 1 $\leq$ Media

Endurance Threshold Criterion 1 is Metric Value $\leq$ Threshold Value 2 satisfied First Program Voltage Level 720 Threshold Value 2 $\leq$ Media Endurance Threshold Criterion 2 is Metric Value $\leq$ Threshold Value 3 satisfied Second Program Voltage Level 730 Threshold Value 3 $\leq$ Media Endurance Threshold Criterion 3 is Metric Value $\leq$ Threshold Value 4 satisfied Third Program Voltage Level (not shown in FIG. 7A)

(101) In some embodiments, to satisfy a threshold criterion a media endurance metric value may be greater than or equal to the threshold value that the threshold criterion is based on. In some embodiments, to satisfy the threshold criterion the media endurance metric value may be greater than the threshold value that the threshold criterion is based on.

(102) FIG. 9 illustrates an example machine of a computer system **900** within which a set of instructions, for causing the machine to perform any one or more of the methodologies discussed herein, can be executed. In some embodiments, the computer system **900** can correspond to a host system (e.g., the host system **120** of FIG. 1) that includes, is coupled to, or utilizes a memory sub-system (e.g., the memory sub-system **110** of FIG. 1) or can be used to perform the operations of a controller (e.g., to execute an operating system to perform operations corresponding to the local media controller **135** of FIG. 1). In alternative embodiments, the machine can be connected (e.g., networked) to other machines in a LAN, an intranet, an extranet, and/or the Internet. The machine can operate in the capacity of a server or a client machine in client-server network environment, as a peer machine in a peer-to-peer (or distributed) network environment, or as a server or a client machine in a cloud computing infrastructure or environment.

(103) The machine can be a personal computer (PC), a tablet PC, a set-top box (STB), a Personal Digital Assistant (PDA), a cellular telephone, a web appliance, a server, a network router, a switch or bridge, or any machine capable of executing a set of instructions (sequential or otherwise) that specify actions to be taken by that machine. Further, while a single machine is illustrated, the term “machine” shall also be taken to include any collection of machines that individually or jointly execute a set (or multiple sets) of instructions to perform any one or more of the methodologies discussed herein.

(104) The example computer system **900** includes a processing device **902**, a main memory **904** (e.g., read-only memory (ROM), flash memory, dynamic random access memory (DRAM) such as synchronous DRAM (SDRAM) or Rambus DRAM (RDRAM), etc.), a static memory **906** (e.g., flash memory, static random access memory (SRAM), etc.), and a data storage system **918**, which communicate with each other via a bus **930**.

(105) Processing device **902** represents one or more general-purpose processing devices such as a microprocessor, a central processing unit, or the like. More particularly, the processing device can be a complex instruction set computing (CISC) microprocessor, reduced instruction set computing (RISC) microprocessor, very long instruction word (VLIW) microprocessor, or a processor implementing other instruction sets, or processors implementing a combination of instruction sets. Processing device **902** can also be one or more special-purpose processing devices such as an application specific integrated circuit (ASIC), a field programmable gate array (FPGA), a digital signal processor (DSP), network processor, or the like. The processing device **902** is configured to execute instructions **926** for performing the operations and steps discussed herein. The computer system **900** can further include a network interface device **908** to communicate over the network **920**.

(106) The data storage system **918** can include a machine-readable storage medium **924** (also known as a computer-readable medium) on which is stored one or more sets of instructions **926** or software embodying any one or more of the methodologies or functions described herein. The instructions **926** can also reside, completely or at least partially, within the main memory **904** and/or within the processing device **902** during execution thereof by the computer system **900**, the main memory **904** and the processing device **902** also constituting machine-readable storage media. The machine-readable storage medium **924**, data storage system **918**, and/or main memory **904** can

correspond to the memory sub-system **110** of FIG. **1**.

(107) In one embodiment, the instructions **926** include instructions to implement functionality corresponding to the local media controller **135** of FIG. **1**). While the machine-readable storage medium **924** is shown in an example embodiment to be a single medium, the term “machine-readable storage medium” should be taken to include a single medium or multiple media that store the one or more sets of instructions. The term “machine-readable storage medium” shall also be taken to include any medium that is capable of storing or encoding a set of instructions for execution by the machine and that cause the machine to perform any one or more of the methodologies of the present disclosure. The term “machine-readable storage medium” shall accordingly be taken to include, but not be limited to, solid-state memories, optical media, and magnetic media.

(108) Some portions of the preceding detailed descriptions have been presented in terms of algorithms and symbolic representations of operations on data bits within a computer memory. These algorithmic descriptions and representations are the ways used by those skilled in the data processing arts to most effectively convey the substance of their work to others skilled in the art. An algorithm is here, and generally, conceived to be a self-consistent sequence of operations leading to a desired result. The operations are those requiring physical manipulations of physical quantities. Usually, though not necessarily, these quantities take the form of electrical or magnetic signals capable of being stored, combined, compared, and otherwise manipulated. It has proven convenient at times, principally for reasons of common usage, to refer to these signals as bits, values, elements, symbols, characters, terms, numbers, or the like.

(109) It should be borne in mind, however, that all of these and similar terms are to be associated with the appropriate physical quantities and are merely convenient labels applied to these quantities. The present disclosure can refer to the action and processes of a computer system, or similar electronic computing device, that manipulates and transforms data represented as physical (electronic) quantities within the computer system's registers and memories into other data similarly represented as physical quantities within the computer system memories or registers or other such information storage systems.

(110) The present disclosure also relates to an apparatus for performing the operations herein. This apparatus can be specially constructed for the intended purposes, or it can include a general purpose computer selectively activated or reconfigured by a computer program stored in the computer. Such a computer program can be stored in a computer readable storage medium, such as, but not limited to, any type of disk including floppy disks, optical disks, CD-ROMs, and magnetic-optical disks, read-only memories (ROMs), random access memories (RAMs), EPROMs, EEPROMs, magnetic or optical cards, or any type of media suitable for storing electronic instructions, each coupled to a computer system bus.

(111) The algorithms and displays presented herein are not inherently related to any particular computer or other apparatus. Various general purpose systems can be used with programs in accordance with the teachings herein, or it can prove convenient to construct a more specialized apparatus to perform the method. The structure for a variety of these systems will appear as set forth in the description below. In addition, the present disclosure is not described with reference to any particular programming language. It will be appreciated that a variety of programming languages can be used to implement the teachings of the disclosure as described herein.

(112) The present disclosure can be provided as a computer program product, or software, that can include a machine-readable medium having stored thereon instructions, which can be used to program a computer system (or other electronic devices) to perform a process according to the present disclosure. A machine-readable medium includes any mechanism for storing information in a form readable by a machine (e.g., a computer). In some embodiments, a machine-readable (e.g., computer-readable) medium includes a machine (e.g., a computer) readable storage medium such as a read only memory (“ROM”), random access memory (“RAM”), magnetic disk storage media,

optical storage media, flash memory components, etc.

(113) In the foregoing specification, embodiments of the disclosure have been described with reference to specific example embodiments thereof. It will be evident that various modifications can be made thereto without departing from the broader spirit and scope of embodiments of the disclosure as set forth in the following claims. The specification and drawings are, accordingly, to be regarded in an illustrative sense rather than a restrictive sense.

Claims

1. A system comprising: an array of memory cells; and a processing device operatively coupled to the array of memory cells, the processing device to perform operations comprising: determining that a media endurance metric value for a string of the array of memory cells satisfies a first threshold criterion based on a first threshold value; and controlling, based on the media endurance metric value, a ramp rate of a program pulse applied to a wordline of the string.
2. The system of claim 1, wherein the operations further comprise: determining that the media endurance metric value does not satisfy the first threshold criterion; and in response to determining that the media endurance metric value does not satisfy the first threshold criterion, setting the ramp rate to a default ramp rate.
3. The system of claim 1, wherein the controlling comprises setting the ramp rate according to a difference between the first threshold value and the media endurance metric value.
4. The system of claim 1, wherein the determining comprises tracking the media endurance metric value over time as a program/erase cycle (PEC) value.
5. The system of claim 1, wherein the array of memory cells is configured as single-level cell (SLC) memory.
6. The system of claim 1, wherein the controlling comprises: in response to determining that the media endurance metric value of the string satisfies the first threshold criterion but not a second threshold criterion based on a second threshold value that is greater than the first threshold value, causing the ramp rate to be set to a first ramp rate; in response to determining that the media endurance metric value of the string satisfies the second threshold criterion but not a third threshold criterion based on a third threshold value that is greater than the second threshold value, causing the ramp rate to be set to a second ramp rate that is lower than the first ramp rate; and in response to determining that the media endurance metric value of the string satisfies the third threshold criterion, causing the ramp rate to be set to a third ramp rate that is lower than the second ramp rate.
7. The system of claim 1, wherein the operations further comprise adjusting, based on the media endurance metric value, a voltage of the program pulse applied to the wordline of the string.
8. The system of claim 7, wherein the adjusting comprises setting the voltage of the program pulse according to a difference between the first threshold value and the media endurance metric value.
9. The system of claim 7, wherein the adjusting comprises: in response to determining that the media endurance metric value of the string satisfies the first threshold criterion but not a second threshold criterion based on a second threshold value that is greater than the first threshold value, causing the voltage of the program pulse to be set to a first program voltage level; in response to determining that the media endurance metric value of the string satisfies the second threshold criterion but not a third threshold criterion based on a third threshold value that is greater than the second threshold value, causing the voltage of the program pulse to be set to a second program voltage level that is higher than the first program voltage level; and in response to determining that the media endurance metric value of the string satisfies the third threshold criterion, causing the voltage of the program pulse to be set to a third program voltage level that is higher than the second program voltage level.
10. A method comprising: accessing, by a processing device, an array of memory cells; determining that a media endurance metric value for a string of the array of memory cells satisfies a first

threshold criterion based on a first threshold value; and controlling, based on the media endurance metric value, a ramp rate of a program pulse applied to a wordline of the string.

11. The method of claim 10, further comprising: determining that the media endurance metric value does not satisfy the first threshold criterion; and in response to determining that the media endurance metric value does not satisfy the first threshold criterion, setting the ramp rate to a default ramp rate.

12. The method of claim 10, wherein the controlling comprises setting the ramp rate according to a difference between the first threshold value and the media endurance metric value.

13. The method of claim 10, wherein the determining comprises tracking the media endurance metric value over time as a PEC value.

14. The method of claim 10, wherein the array of memory cells is configured as SLC memory.

15. The method of claim 10, wherein the controlling comprises: in response to determining that the media endurance metric value of the string satisfies the first threshold criterion but not a second threshold criterion based on a second threshold value that is greater than the first threshold value, causing the ramp rate to be set to a first ramp rate; in response to determining that the media endurance metric value of the string satisfies the second threshold criterion but not a third threshold criterion based on a third threshold value that is greater than the second threshold value, causing the ramp rate to be set to a second ramp rate that is lower than the first ramp rate; and in response to determining that the media endurance metric value of the string satisfies the third threshold criterion, causing the ramp rate to be set to a third ramp rate that is lower than the second ramp rate.

16. The method of claim 10, further comprising adjusting, based on the media endurance metric value, a voltage of the program pulse applied to the wordline of the string.

17. The method of claim 16, wherein the adjusting comprises setting the voltage of the program pulse according to a difference between the first threshold value and the media endurance metric value.

18. The method of claim 16, wherein the adjusting comprises: in response to determining that the media endurance metric value of the string satisfies the first threshold criterion but not a second threshold criterion based on a second threshold value that is greater than the first threshold value, causing the voltage of the program pulse to be set to a first program voltage level; in response to determining that the media endurance metric value of the string satisfies the second threshold criterion but not a third threshold criterion based on a third threshold value that is greater than the second threshold value, causing the voltage of the program pulse to be set to a second program voltage level that is higher than the first program voltage level; and in response to determining that the media endurance metric value of the string satisfies the third threshold criterion, causing the voltage of the program pulse to be set to a third program voltage level that is higher than the second program voltage level.

19. A non-transitory computer-readable storage medium storing instructions, which when executed by a processing device coupled to an array of memory cells, cause the processing device to perform operations comprising: determining a media endurance metric value for a string of the array of memory cells; in response to the determining that the media endurance metric value satisfies a first threshold criterion, controlling, based on the media endurance metric value, a ramp rate of a program pulse applied to a wordline of the string; and in response to determining that the media endurance metric value does not satisfy the first threshold criterion, setting the ramp rate to a default ramp rate.

20. The non-transitory computer-readable storage medium of claim 19, wherein the controlling comprises: in response to determining that the media endurance metric value of the string satisfies the first threshold criterion based on a first threshold value but not a second threshold criterion based on a second threshold value that is greater than the first threshold value, causing the ramp rate to be set to a first ramp rate; in response to determining that the media endurance metric value of the string satisfies the second threshold criterion but not a third threshold criterion based on a

third threshold value that is greater than the second threshold value, causing the ramp rate to be set to a second ramp rate that is lower than the first ramp rate; and in response to determining that the media endurance metric value of the string satisfies the third threshold criterion, causing the ramp rate to be set to a third ramp rate that is lower than the second ramp rate.
