

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287589

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

YANG; Yonggang

THREE-DIMENSIONAL MEMORY DEVICES AND METHODS FOR FORMING THE SAME

Abstract

In certain aspects, a memory device includes a semiconductor layer and a stack structure over the semiconductor layer. The stack structure includes alternating first layers and first dielectric layers. The first layers in a first portion of the stack structure include second dielectric layers, and the first layers in a second portion adjacent to the first portion of the stack structure include conductive layers. The memory device further includes a third dielectric layer over the stack structure and a contact structure. The contact structure extends through the third dielectric layer and a part of the first portion of the stack structure to be connected with a first one of the conductive layers. The contact structure includes a first contact segment and a second contact segment that are connected with each other at a first joint region in the third dielectric layer.

Inventors: YANG; Yonggang (Wuhan, CN)

Applicant: YANGTZE MEMORY TECHNOLOGIES CO., LTD. (Wuhan, CN)

Family ID: 90826622

Appl. No.: 18/631771

Filed: April 10, 2024

Related U.S. Application Data

parent WO continuation PCT/CN2024/080913 20240311 PENDING child US 18631771

Publication Classification

Int. Cl.: H10B43/27 (20230101)

U.S. Cl.:

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation of International Application No. PCT/CN2024/080913, filed on Mar. 11, 2024, entitled “THREE-DIMENSIONAL MEMORY DEVICES AND METHODS FOR FORMING THE SAME,” which is incorporated herein by reference in its entirety.

BACKGROUND

[0002] The present disclosure relates to three-dimensional (3D) memory devices and fabrication methods thereof.

[0003] Planar memory cells are scaled to smaller sizes by improving process technology, circuit design, programming algorithm, and fabrication process. However, as feature sizes of the memory cells approach a lower limit, planar process and fabrication techniques become challenging and costly. As a result, memory density for planar memory cells approaches an upper limit.

[0004] A 3D memory architecture can address the density limitation in planar memory cells. The 3D memory architecture includes a memory array and peripheral devices for controlling signals to and from the memory array.

SUMMARY

[0005] In one aspect, a memory device includes a semiconductor layer and a stack structure over the semiconductor layer. The stack structure includes alternating first layers and first dielectric layers. The first layers in a first portion of the stack structure include second dielectric layers, and the first layers in a second portion adjacent to the first portion of the stack structure include conductive layers. The memory device further includes a third dielectric layer over the stack structure and a contact structure. The contact structure extends through the third dielectric layer and a part of the first portion of the stack structure to be connected with a first one of the conductive layers. The contact structure includes a first contact segment and a second contact segment which are connected with each other at a first joint region in the third dielectric layer.

[0006] In some implementations, the first contact segment extends through a first part of the third dielectric layer in a first direction. The second contact segment extends through a second part of the third dielectric layer and the part of the stack structure in the first direction.

[0007] In some implementations, a size of the first contact segment is greater than a size of the second contact segment in a second direction perpendicular to the first direction.

[0008] In some implementations, the contact structure includes a vertical contact member extending in a first direction and a lateral contact member connecting to the vertical contact member and extending in a second direction. The lateral contact member connects with the first one of the conductive layers.

[0009] In some implementations, the first contact segment includes a first part of the vertical contact member. The second contact segment includes a second part of the vertical contact member and the spacer. The first part and the second part of the vertical contact member connect with each other at the first joint region in the third dielectric layer.

[0010] In some implementations, the contact structure further includes a filler body surrounded by the vertical contact member. The first contact segment further includes a first part of the filler body, and the second contact segment further includes a second part of the filler body. The first part and the second part of the filler body connect with each other at the first joint region in the third dielectric layer.

[0011] In some implementations, the second dielectric layers in the first portion of the stack structure include a first one of the second dielectric layers at a same level as the first one of the

conductive layers and a second one of the second dielectric layers at a same level as a second one of the conductive layers. An end surface of the second one of the conductive layers is covered by a first high dielectric constant (high-k) gate dielectric layer, and the second one of the conductive layers connects with the second one of the second dielectric layers via the first high-k gate dielectric layer. The lateral contact member of the contact structure protrudes into the second portion of the stack structure and connects with the first one of the conductive layers.

[0012] In some implementations, side surfaces of the first one of the conductive layers are surrounded by second high-k gate dielectric layers. Side surfaces of the second one of the conductive layers are surrounded by third high-k gate dielectric layers.

[0013] In some implementations, the lateral contact member and the first one of the conductive layers include different materials.

[0014] In some implementations, the lateral contact member and the first one of the conductive layers include Titanium nitride and tungsten, respectively.

[0015] In some implementations, the memory device further includes a slit structure including a first slit segment and a second slit segment. The first slit segment extends through a third part of the third dielectric layer. The second slit segment extends through a fourth part of the third dielectric layer, the first portion of the stack structure, and a part of the semiconductor layer. The first slit segment connects with the second slit segment at a second joint region in the third dielectric layer.

[0016] In some implementations, a first distance from the slit structure to an end surface of the first one of the conductive layers in the second direction is smaller than a second distance from the slit structure to the end surface of the second one of the conductive layers in the second direction.

[0017] In some implementations, a size of the first slit segment is greater than a size of the second slit segment in the second direction.

[0018] In another aspect, a method for forming a memory device is disclosed. The method includes forming a stack structure over a semiconductor layer. The stack structure includes alternating first dielectric layers and second dielectric layers. The method also includes forming a third dielectric layer over the stack structure and forming a contact structure extending through the third dielectric layer and a part of the stack structure. The contact structure includes a first contact segment and a second contact segment that are connected with each other at a first joint region in the third dielectric layer.

[0019] In some implementations, forming the contact structure includes forming a spacer, forming a vertical contact member extending in a first direction and a lateral contact member extending in a second direction perpendicular to the first direction, and forming a filler body. The vertical contact member connects with the lateral contact member, and at least a part of the vertical contact member is surrounded by the spacer. The filler body is surrounded by the vertical contact member.

[0020] In some implementations, prior to forming the contact structure, the method further includes forming a first slit opening extending through the stack structure and a part of the semiconductor layer. The method also includes filling the first slit opening with a preliminary slit structure. Forming the third dielectric layer includes depositing a first dielectric sub-layer over the stack structure to cover the preliminary slit structure. The third dielectric layer includes the first dielectric sub-layer.

[0021] In some implementations, forming the contact structure further includes forming a first contact opening extending through the first dielectric sub-layer and the part of the stack structure. Forming the spacer includes depositing a first dielectric material on a sidewall of the first contact opening.

[0022] In some implementations, forming the vertical contact member and the lateral contact member includes forming a lateral recess below a bottom of the first contact opening by removing a part of a first one of the second dielectric layers exposed at the bottom of the first contact opening, and filling the first contact opening and the lateral recess with a second dielectric material

different from that of the first dielectric layers and the second dielectric layers.

[0023] In some implementations, forming the third dielectric layer further includes depositing a second dielectric sub-layer over the first dielectric sub-layer to cover the second dielectric material filled in the first contact opening. The third dielectric layer further includes the second dielectric sub-layer.

[0024] In some implementations, the stack structure includes a first portion and a second portion adjacent to the first portion, and the contact structure extends through the third dielectric layer and a part of the first portion of the stack structure. The method further includes performing a gate line replacement process to replace parts of the second dielectric layers in the second portion of the stack structure with conductive layers.

[0025] In some implementations, performing the gate line replacement process includes forming a second slit opening to expose the preliminary slit structure, removing the preliminary slit structure to expose the first slit opening through the second slit opening, removing the parts of the second dielectric layers in the second portion of the stack structure through the first slit opening to form a plurality of lateral openings, forming high-k gate dielectric layers on walls of the plurality of lateral openings, filling the plurality of lateral openings with a first conductive material to form the conductive layers such that end surfaces and side surfaces of the conductive layers are surrounded by the high-k gate dielectric layers, respectively, and forming a slit structure to fill the first slit opening and the second slit opening.

[0026] In some implementations, the lateral recess filled with the first dielectric material protrudes into the second portion of the stack structure and connects with a first corresponding high-k gate dielectric layer on an end surface of a first one of the conductive layers. A second one of the second dielectric layers in the first portion of the stack structure connects with a second corresponding high-k gate dielectric layer at an end surface of a second one of the conductive layers.

[0027] In some implementations, forming the third dielectric layer further includes depositing a third dielectric sub-layer over the second dielectric sub-layer to cover the slit structure formed in the first and second slit openings. The third dielectric layer further includes the third dielectric sub-layer.

[0028] In some implementations, forming the vertical contact member and the lateral contact member further includes forming a second contact opening in the third dielectric layer to expose the second dielectric material filled in the first contact opening, removing the second dielectric material through the second contact opening to expose the lateral recess and a sidewall of the spacer, removing the first corresponding high-k gate dielectric layer on the end surface of the first one of the conductive layers to expose the end surface of the first one of the conductive layers, and depositing a second conductive material to fill the lateral recess, on the sidewall of the spacer, and on a sidewall of the second contact opening to form the lateral contact member and the vertical contact member, respectively. A size of the second contact opening is greater than a size of the first contact opening in the second direction.

[0029] In some implementations, the lateral contact member of the contact structure protrudes into the second portion of the stack structure and connects with the first one of the conductive layers.

[0030] In some implementations, the first joint region comprises a region where the first contact opening connects with the second contact opening in the third dielectric layer.

[0031] In some implementations, forming the filler body includes filling a remaining space of the first contact opening and a remaining space of the second contact opening with a third dielectric material.

[0032] In some implementations, the slit structure includes a first slit segment filling the first slit opening and a second slit segment filling the second slit opening. The first slit segment connects with the second slit segment at a second joint region in the third dielectric layer. A size of the first slit segment is greater than a size of the second slit segment in the second direction.

[0033] In some implementations, a first distance from the slit structure to the end surface of the

first one of the conductive layers in the second direction is smaller than a second distance from the slit structure to the end surface of the second one of the conductive layers in the second direction.

[0034] In some implementations, the first contact segment includes a first part of the vertical contact member and a first part of the filler body. The second contact segment includes a second part of the vertical contact member, and a second part of the filler body. The first part and the second part of the vertical contact member connect with each other at the first joint region in the third dielectric layer. The first part and the second part of the filler body connect with each other at the first joint region in the third dielectric layer. A size of the first contact segment is greater than a size of the second contact segment in the second direction perpendicular to the first direction.

[0035] In still another aspect, a system includes a memory device and a memory controller coupled to the memory device and configured to control an operation of the memory device. The memory device includes a semiconductor layer and a stack structure over the semiconductor layer. The stack structure includes alternating first layers and first dielectric layers. The first layers in a first portion of the stack structure include second dielectric layers, and the first layers in a second portion adjacent to the first portion of the stack structure include conductive layers. The memory device further includes a third dielectric layer over the stack structure and a contact structure. The contact structure extends through the third dielectric layer and a part of the first portion of the stack structure to be connected with a first one of the conductive layers. The contact structure includes a first contact segment and a second contact segment that are connected with each other at a first joint region in the third dielectric layer.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0036] The accompanying drawings, which are incorporated herein and form a part of the specification, illustrate aspects of the present disclosure and, together with the description, further serve to explain the principles of the present disclosure and to enable a person skilled in the pertinent art to make and use the present disclosure.

[0037] FIG. 1 illustrates a plan view of a 3D memory device having contact structures, according to some aspects of the present disclosure.

[0038] FIG. 2 illustrates cross-sectional side views of a 3D memory device having contact structures, according to some examples of the present disclosure.

[0039] FIGS. 3A-3C illustrate some steps in a fabrication process for forming the 3D memory device of FIG. 2, according to some examples of the present disclosure.

[0040] FIG. 4 illustrates cross-sectional side views of a 3D memory device having contact structures, according to some aspects of the present disclosure.

[0041] FIG. 5A illustrates a cross-sectional side view of a 3D memory device having contact structures, according to some aspects of the present disclosure.

[0042] FIG. 5B illustrates an enlarged cross-sectional side view of a 3D memory device having contact structures, according to some aspects of the present disclosure.

[0043] FIG. 5C illustrates a slit structure in a 3D memory device, according to some aspects of the present disclosure.

[0044] FIGS. 6A-6R illustrate a fabrication process for forming a 3D memory device having contact structures, according to some aspects of the present disclosure.

[0045] FIG. 7 is a flowchart of a method for forming a 3D memory device having contact structures, according to some aspects of the present disclosure.

[0046] FIG. 8 illustrates a block diagram of an example system having a 3D memory device, according to some aspects of the present disclosure.

[0047] FIG. 9A illustrates a diagram of an example memory card having a 3D memory device,

according to some aspects of the present disclosure.

[0048] FIG. 9B illustrates a diagram of an example solid-state drive (SSD) having a 3D memory device, according to some aspects of the present disclosure.

[0049] The present disclosure will be described with reference to the accompanying drawings.

DETAILED DESCRIPTION

[0050] Although specific configurations and arrangements are discussed, it should be understood that this is done for illustrative purposes only. As such, other configurations and arrangements can be used without departing from the scope of the present disclosure. Also, the present disclosure can also be employed in a variety of other applications. Functional and structural features as described in the present disclosures can be combined, adjusted, and modified with one another and in ways not specifically depicted in the drawings, such that these combinations, adjustments, and modifications are within the scope of the present disclosure.

[0051] In general, terminology may be understood at least in part from usage in context. For example, the term “one or more” as used herein, depending at least in part upon context, may be used to describe any feature, structure, or characteristic in a singular sense or may be used to describe combinations of features, structures or characteristics in a plural sense. Similarly, terms, such as “a,” “an,” or “the,” again, may be understood to convey a singular usage or to convey a plural usage, depending at least in part upon context. In addition, the term “based on” may be understood as not necessarily intended to convey an exclusive set of factors and may, instead, allow for existence of additional factors not necessarily expressly described, again, depending at least in part on context.

[0052] It should be readily understood that the meaning of “on,” “above,” and “over” in the present disclosure should be interpreted in the broadest manner such that “on” not only means “directly on” something but also includes the meaning of “on” something with an intermediate feature or a layer therebetween, and that “above” or “over” not only means the meaning of “above” or “over” something but can also include the meaning it is “above” or “over” something with no intermediate feature or layer therebetween (i.e., directly on something).

[0053] Further, spatially relative terms, such as “beneath,” “below,” “lower,” “above,” “upper,” and the like, may be used herein for ease of description to describe one element or feature's relationship to another element(s) or feature(s) as illustrated in the figures. The spatially relative terms are intended to encompass different orientations of the device in use or operation in addition to the orientation depicted in the figures. The apparatus may be otherwise oriented (rotated 90 degrees or at other orientations) and the spatially relative descriptors used herein may likewise be interpreted accordingly.

[0054] As used herein, the term “substrate” refers to a material onto which subsequent material layers are added. The substrate itself can be patterned. Materials added on top of the substrate can be patterned or can remain unpatterned. Furthermore, the substrate can include a wide array of semiconductor materials, such as silicon, germanium, gallium arsenide, indium phosphide, etc. Alternatively, the substrate can be made from an electrically non-conductive material, such as a glass, a plastic, or a sapphire wafer.

[0055] As used herein, the term “layer” refers to a material portion including a region with a thickness. A layer can extend over the entirety of an underlying or overlying structure or may have an extent less than the extent of an underlying or overlying structure. Further, a layer can be a region of a homogeneous or inhomogeneous continuous structure that has a thickness less than the thickness of the continuous structure. For example, a layer can be located between any pair of horizontal planes between, or at, a top surface and a bottom surface of the continuous structure. A layer can extend horizontally, vertically, and/or along a tapered surface. A substrate can be a layer, can include one or more layers therein, and/or can have one or more layers thereupon, thereabove, and/or therebelow. A layer can include multiple layers. For example, an interconnect layer can include one or more conductors and contact layers (in which interconnect lines and/or vertical

contacts are formed) and one or more dielectric layers.

[0056] In some implementations, a 3D memory device may include a substrate and a stack structure over the substrate. The stack structure may include a first portion and a second portion adjacent to the first portion. The first portion of the stack structure may include alternating first dielectric layers and second dielectric layers, and the second portion of the stack structure may include alternating first dielectric layers and conductive layers. A contact structure (e.g., an example word line pick-up structure) may extend through a part of the first portion of the stack structure and connect with a first one of the conductive layers in the second portion. In some implementations, the contact structure may include a spacer, a vertical contact member formed on a sidewall of the spacer, and a lateral contact member in contact with the vertical contact member and connecting to the first one of the conductive layers.

[0057] To form the 3D memory device, initially, the stack structure having alternating first dielectric layers and second dielectric layers can be formed (e.g., initially, both the first and second portions of the stack structure include alternating first dielectric layers and second dielectric layers). Subsequently, a gate line replacement process can be performed in the second portion of the stack structure to replace the second dielectric layers in the second portion with conductive layers, respectively. High-k gate dielectric layers may be formed prior to the formation of the conductive layers, such that the conductive layers may be formed surrounded by the high-k gate dielectric layers. Afterwards, the contact structure may be formed in the first portion of the stack structure at least by: (a) forming a contact opening extending through a part of the first portion of the stack structure; (b) forming the spacer on a sidewall of the contact opening; (c) removing part of a first one of the second dielectric layers exposed from the bottom of the contact opening by wet etching to form a lateral recess; (d) forming a lateral contact member by depositing a conductive material through the contact opening to fill the lateral recess, such that the lateral contact member connects with the first one of the conductive layers; and (e) forming the vertical contact member in contact with the lateral contact member by depositing the conductive material on a sidewall of the spacer.

[0058] In the above step (c), the part of the first one of the second dielectric layers (including silicon nitride) can be wet etched by applying a wet etchant through the contact opening. However, as described below in more detail with reference to FIGS. 3B-3C, when the part of the first one of the second dielectric layers is etched away by the wet etchant, the high-k gate dielectric layers surrounding the first one of the conductive layers may be over-etched by the wet etchant, resulting in damage in the high-k gate dielectric layers surrounding the first one of the conductive layers. If the high-k gate dielectric layers surrounding the first one of the conductive layers is over etched too much, a spacer of a slit structure in the memory device can also be damaged. It can be difficult to find an appropriate wet etchant or develop a new wet etchant that can be controlled to only etch the first one of the second dielectric layers without over-etching the high-k gate dielectric layers surrounding the first one of the conductive layers. Also, it can be difficult to control an etching rate and/or etching time to remove only the part of the first one of the second dielectric layers that is enough to expose an end surface of the first one of the conductive layers, without over-etching the high-k gate dielectric layers surrounding the first one of the conductive layers.

[0059] An example solution to solve the over-etching issue of the high-k gate dielectric layers may include: (1) before forming the lateral contact member, depositing a high-k dielectric material through the lateral recess to repair the damage made to the high-k gate dielectric layers surrounding the first one of the conductive layers; (2) etching back only a high-k gate dielectric layer formed on the end surface of the first one of the conductive layers to expose the end surface of the first one of the conductive layers; and then (3) forming the lateral contact member to connect with the end surface of the first one of the conductive layers. In this case, since (1) additional high-k dielectric material is deposited to repair the damage made to the high-k gate dielectric layers and (2) the high-k gate dielectric layer formed on the end surface of the first one of the conductive layers is

etched back again, the manufacturing process of the memory device becomes more complicated, and the cost of the memory device is increased.

[0060] To address one or more of the aforementioned issues, the present disclosure introduces a solution that can avoid the over-etching issue of the high-k gate dielectric layers. For example, in the solution disclosed herein, the contact opening and the lateral recess of the contact structure can be formed in the first portion of the stack structure before the gate line replacement process. A dielectric material (such as polysilicon) can be filled in the contact opening and the lateral recess. Then, the gate line replacement process can be performed to form the conductive layers in the second portion of the stack structure. High-k gate dielectric layers may be formed prior to the formation of the conductive layers, such that the conductive layers may be surrounded by the high-k gate dielectric layers. Afterwards, the dielectric material (such as polysilicon) filled in the contact opening and the lateral recess can be removed to expose a high-k gate dielectric layer formed on an end surface of the first one of the conductive layers. In this case, it is relatively easy to perform and control a wet etch to etch away only the dielectric material filled in the lateral recess without damaging the high-k gate dielectric layers surrounding the first one of the conductive layers. Then, the high-k gate dielectric layer on the end surface of the first one of the conductive layers can be removed to expose the end surface of the first one of the conductive layers. Subsequently, the lateral contact member can be formed in the lateral recess in contact with the end surface of the first one of the conductive layers. In the solution disclosed herein, there is no need to develop new wet etchants to avoid the over-etching issue. The etching process can be controlled, and no damage is made to the high-k gate dielectric layers. That is, the over-etching issue of the high-k gate dielectric layers can be avoided. As a result, the manufacture cost of the memory device can be reduced.

[0061] FIG. 1 illustrates a plan view of a 3D memory device **100** having contact structures **106**, according to some aspects of the present disclosure. In some implementations, 3D memory device **100** is a NAND Flash memory device in which memory cells are provided in the form of an array of NAND memory strings. It is noted that x and y axes are included in FIG. 1 to illustrate two orthogonal (perpendicular) directions in the wafer plane. The x-direction is the word line direction of 3D memory device **100**, and the y-direction is the bit line direction of 3D memory device **100**.

[0062] As shown in FIG. 1, 3D memory device **100** can include one or more blocks **102** arranged in the y-direction (the bit line direction) separated by parallel slit structures **108**, such as gate line slits (GLSs). In some implementations in which 3D memory device **100** is a NAND Flash memory device, each block **102** is the smallest erasable unit of the NAND Flash memory device. Each block **102** can further include multiple fingers **104** in the y-direction separated by some slit structures **108** with “H” cuts **109**.

[0063] As shown in FIG. 1, 3D memory device **100** can be divided into at least a core array region **101** in which an array of channel structures **110** are formed, as well as a word line pick-up region **103** in which contact structures **106** are formed. Core array region **101** and word line pick-up region **103** are arranged in the x-direction (the word line direction), according to some implementations. It is understood that although one core array region **101** and one word line pick-up region **103** are illustrated in FIG. 1, multiple core array regions **101** and/or multiple word line pick-up regions **103** may be included in 3D memory device **100**, for example, one word line pick-up region **103** between two core array regions **101** in the x-direction, in other examples. It is also understood that FIG. 1 only illustrates portions of core array region **101** that are adjacent to word line pick-up region **103**.

[0064] As described below in detail, word line pick-up region **103** can include conductive portions **105** and dielectric portions **107** arranged in the y-direction. As shown in FIG. 1, contact structures **106** are disposed in dielectric portion **107**, while dummy channel structures **112** are disposed in conductive portion **105** of word line pick-up region **103** to provide mechanical support and/or load balancing, according to some implementations. In some implementations, dummy channel

structures **112** are disposed in dielectric portion **107** of word line pick-up region **103** as well, for example, between contact structures **106** in the x-direction. In some other implementations, dummy channel structures **112** are not disposed in dielectric portion **107** of word line pick-up region **103**, i.e., only in conductive portion **105** of word line pick-up region **103**. As shown in FIG. 1, each finger **104** of 3D memory device **100** can include one row of contact structures **106** disposed in dielectric portion **107** of word line pick-up region **103**. It is understood that the layout and arrangement of contact structures **106**, as well as the shape of each contact structure **106**, may vary in different examples.

[0065] FIG. 2 illustrates cross-sectional side views of a 3D memory device **200** having contact structures **106**, according to some examples of the present disclosure. 3D memory device **200** can be an example implementation of 3D memory device **100** of FIG. 1. One cross-section may be along the BB direction in core array region **101** in FIG. 1, and another cross-section may be along the CC direction in word line pick-up region **103** in FIG. 1.

[0066] As shown in FIG. 2, a stack structure **201** can be formed on a substrate **203**, which can include silicon (e.g., single crystalline silicon), silicon germanium (SiGe), gallium arsenide (GaAs), germanium (Ge), silicon on insulator (SOI), or any other suitable materials. In some implementations, substrate **203** includes single crystalline silicon, which is part of the wafer on which 3D memory device **200** is fabricated, either in its native thickness or being thinned. In some implementations, substrate **203** includes, for example, polysilicon, which is a semiconductor layer replacing the part of wafer on which 3D memory device **200** is fabricated. It is noted that y and z axes are included in FIG. 2 to further illustrate the spatial relationship of the components in 3D memory device **200**. Substrate **203** of 3D memory device **200** includes two lateral surfaces extending laterally in the x-y plane: a top surface on the front side of the wafer on which stack structure **201** can be formed, and a bottom surface on the backside opposite to the front side of the wafer. The z-axis is perpendicular to both the x and y axes. As used herein, whether one component (e.g., a layer or a device) is “on,” “above,” or “below” another component (e.g., a layer or a device) of 3D memory device **200** is determined relative to substrate **203** of 3D memory device **200** in the z-direction (the vertical direction perpendicular to the x-y plane) when substrate **203** is positioned in the lowest plane of 3D memory device **200** in the z-direction. The same notion for describing the spatial relationship is applied throughout the present disclosure.

[0067] Stack structure **201** may include a first portion and a second portion. For example, the first portion of stack structure **201** may include a first part of stack structure **201** in dielectric portion **107** of word line pick-up region **103**. The second portion of stack structure **201** may include a second part of stack structure **201** in conductive portion **105** of word line pick-up region **103** and a third part of stack structure **201** in core array region **101**.

[0068] As shown in FIG. 2, stack structure **201** can include vertically interleaved first layers and first dielectric layer **223**. First layers and first dielectric layer **223** can alternate in the vertical direction (the z-direction). In some implementations, stack structure **201** can include a plurality of layer pairs stacked vertically in the z-direction, each of which includes a first layer and a first dielectric layer **223**. The number of the layer pairs in stack structure **201** can determine the number of memory cells in 3D memory device **200**.

[0069] In some implementations, 3D memory device **200** is a NAND Flash memory device, and stack structure **201** is a stacked storage structure through which NAND memory strings are formed. As shown in FIG. 2, the first layers can have different materials in different regions/portions of 3D memory device **200**. For example, the first layers may include second dielectric layers **225** in the first portion of stack structure **201**. That is, the first portion of stack structure **201** (in dielectric portion **107** of word line pick-up region **103**) may include interleaved second dielectric layers **225** and first dielectric layers **223**. The first layers may include conductive layers **222** in the second portion of stack structure **201**. That is, the second portion of stack structure **201** (in core array region **101** and conductive portion **105** of word line pick-up region **103**) may include interleaved

conductive layers **222** and first dielectric layers **223**.

[0070] In some implementations, each conductive layer **222** in core array region **101** and conductive portion **105** of word line pick-up region **103** functions as a gate line of the NAND memory strings (in the forms of channel structures **110**) in core array region **101**, as well as a word line extending laterally from the gate line and ending in conductive portion **105** of word line pick-up region **103** for word line pick-up/fan-out through contact structures **106**. The word lines (i.e., conductive layers **222**) at different depths/levels each extend laterally in core array region **101** and conductive portion **105** of word line pick-up region **103**, but are discontinuous (e.g., being replaced by second dielectric layers **225**) in dielectric portion **107** of word line pick-up region **103**, according to some implementations.

[0071] Conductive layers **222** can include conductive materials including, but not limited to, tungsten (W), cobalt (Co), copper (Cu), aluminum (Al), titanium nitride (TiN), polycrystalline silicon (polysilicon), doped silicon, silicides, or any combination thereof. The dielectric layers can include dielectric materials including, but not limited to, silicon oxide, silicon nitride, silicon oxynitride, or any combination thereof. First dielectric layers **223** and second dielectric layers **225** can have different dielectric materials, such as silicon oxide and silicon nitride. In some implementations, conductive layers **222** include metals, such as tungsten, first dielectric layers **223** include silicon oxide, and second dielectric layers **225** include silicon nitride. For example, first dielectric layers **223** of stack structure **201** may include silicon oxide across core array region **101** and word line pick-up region **103**; conductive layers **222** of stack structure **201** may include tungsten in core array region **101** and conductive portion **105** of word line pick-up region **103**; and second dielectric layers **225** of stack structure **201** may include silicon nitride in dielectric portion **107** of word line pick-up region **103**.

[0072] As shown in FIG. 2, 3D memory device **200** can include channel structures **110** in core array region **101**. Each channel structure **110** can extend vertically through interleaved conductive layers **222** (word lines, e.g., tungsten) and first dielectric layers **223** (e.g., silicon oxide) in stack structure **201** into substrate **203**. 3D memory device **200** can also include dummy channel structures **112** in conductive portion **105** of word line pick-up region **103**. Each dummy channel structure **112** can extend vertically through interleaved conductive layers **222** and first dielectric layers **223** of stack structure **201** into substrate **203**. 3D memory device **200** can further include slit structures **108** across core array region **101** and word line pick-up region **103**. Each slit structure **108** can extend vertically through interleaved conductive layers **222** and first dielectric layers **223** of stack structure **201** into substrate **203** as well.

[0073] As shown in FIG. 2, slit structure **108** can include a slit spacer **229** that separates conductive layers **222** (word lines) between different blocks **102**. In some implementations, slit structure **108** is an insulating structure that does not include any contact therein (i.e., not functioning as the source contact) and thus, does not introduce parasitic capacitance and leakage current with conductive layers **222** (word lines). In some implementations, slit structure **108** is a front-side source contact further including a conductive portion (e.g., including W, polysilicon, and/or TiN) circumscribed by slit spacer **229**. As described below in detail, during the gate line replacement process, a slit opening in which slit structure **108** is formed can serve as the passageway and starting point for forming conductive layers **222**. As a result, slit structure **108** is surrounded by conductive layers **222** in either core array region **101** or conductive portion **105** of word line pick-up region **103**.

[0074] As shown in FIG. 2, in some implementations, 3D memory device **200** further includes a plurality of drain select gate (DSG) channel structures **227** above and in contact with the upper ends of channel structures **110**, respectively. 3D memory device **200** can further include a DSG layer **224** including a semiconductor layer (e.g., polysilicon layer) on stack structure **201** in core array region **101**, but not in word line pick-up region **103**, for example, as shown in FIG. 2. Each DSG channel structure **227** can extend vertically through DSG layer **224** to be in contact with the upper end of a corresponding channel structure **110**. In some implementations, 3D memory device

200 further includes a stop layer **231** (e.g., silicon nitride layer) on DSG layer **224**. DSG channel structure **227** can include a semiconductor layer (e.g., polysilicon) and a spacer surrounding the semiconductor layer. In some implementations, 3D memory device **200** includes a DSG stack including one or more DSG layers and one or more dielectric layers (e.g., silicon oxide layers) stacked above stack structure **201**.

[0075] As shown in FIG. 2, 3D memory device **200** can further include a local contact layer above stop layer **231** and stack structure **201**. In some implementations, the local contact layer includes various local contacts, such as channel contacts **226** (a.k.a. bit line contacts) above and in contact with DSG channel structures **227** in core array region **101**. The local contact layer can further include one or more interlayer dielectric (ILD) layers (also known as “intermetal dielectric (IMD) layers”) in which the local contacts can form. Channel contacts **226** in the local contact layer can include conductive materials including, but not limited to, W, Co, Cu, Al, silicides, or any combination thereof. The ILD layers in the local contact layer can include dielectric materials including, but not limited to, silicon oxide, silicon nitride, silicon oxynitride, low-k dielectrics, or any combination thereof.

[0076] Instead of having staircase structures and word line contacts landed on different levels/stairs of the staircase structures, 3D memory device **200** can include stack structure **201** with uniform heights and contact structures **106** in dielectric portion **107** of word line pick-up region **103** for word line pick-up/fan-out. Each contact structure **106** may include a vertical contact member **202**, a contact spacer **204** circumscribing vertical contact member **202**, and a lateral contact member **206** below and in contact with vertical contact member **202**. Vertical contact member **202** and lateral contact member **206** can include conductive materials including, but not limited to, W, Co, Cu, Al, TiN, polysilicon, doped silicon, silicides, or any combination thereof. Contact spacer **204** can include dielectric materials including, but not limited to, silicon oxide, silicon nitride, silicon oxynitride, or any combination thereof. In some implementations, vertical contact member **202** and lateral contact member **206** include TiN/W, and contact spacer **204** includes silicon oxide.

[0077] In some implementations as shown in FIG. 2, contact structure **106** further includes a filler body **208** circumscribed by vertical contact member **202**. That is, a contact opening of contact structure **106** may not be fully filled with contact spacer **204** and vertical contact member **202**, and the remaining space of the contact opening may be filled with dielectric materials, including, but not limited to, silicon oxide, silicon nitride, silicon oxynitride, or any combination thereof, as filler body **208**.

[0078] As shown in FIG. 2, lateral contact member **206** of each contact structure **106** in dielectric portion **107** can extend laterally in the y-direction (the bit line direction) to be in contact with a corresponding conductive layer **222** (word line) in conductive portion **105** at the same level as stack structure **201**. Since lateral contact member **206** is in contact with vertical contact member **202** of contact structure **106**, each contact structure **106** is electrically connected to corresponding conductive layer **222** (word line) across conductive portion **105** in word line pick-up region **103** and core array region **101**, according to some implementations. In other words, contact structures **106** can extend vertically through stack structure **201** at different depths to be electrically connected to the word lines at different levels, respectively, to achieve word line pick-up/fan-out.

[0079] As described below in detail, during the gate line replacement process, some of second dielectric layers **225** (e.g., silicon nitride) remain intact in dielectric portion **107** of word line pick-up region **103**, and contact structure **106** is formed by etching first and second dielectric layers **223** and **225** in dielectric portion **107** of word line pick-up region **103**. As a result, contact structures **106** extend into interleaved first and second dielectric layers **223** and **225** and are surrounded by first and second dielectric layers **223** and **225** in dielectric portion **107** of word line pick-up region **103**. The bottom of each contact structure **106** can be aligned with a corresponding second dielectric layer **225**, as opposed to first dielectric layer **223**, and the corresponding second dielectric layer **225** can be partially replaced with lateral contact member **206** to form the electrical

connection between vertical contact member **202** of contact structure **106** and the corresponding conductive layer **222** (word line). Thus, in some implementations, lateral contact member **206** is sandwiched between two first dielectric layers **223**, as opposed to two second dielectric layers **225**, in dielectric portion **107** of word line pick-up region **103**.

[0080] As shown in FIG. 2, 3D memory device **200** can further include high dielectric constant (high-k) gate dielectric layers **220** each sandwiched between adjacent conductive layer **222** and first dielectric layer **223** in core array region **101** and conductive portion **105** of word line pick-up region **103**. As described below in detail with respect to the fabrication process, high-k gate dielectric layers **220** may be formed prior to the formation of conductive layers **222**, such that conductive layers **222** may be formed surrounded by high-k gate dielectric layers **220**. High-k gate dielectric layers **220** can include high-k dielectric materials, such as aluminum oxide (AlO), hafnium oxide (HfO), zirconium oxide (ZrO), or any combinations thereof.

[0081] Compared with other high-k gate dielectric layers **220**, part of high-k gate dielectric layers **220** surrounding a corresponding conductive layer **222** (part of word line) that is in contact with lateral contact member **206** is removed to expose conductive layer **222** such that lateral contact member **206** can be electrically connected to conductive layer **222**. However, as described below in more detail with reference to FIGS. 3B-3C, high-k gate dielectric layers **220** surrounding the corresponding conductive layer **222** may be over-etched during the fabrication process, causing damage to high-k gate dielectric layers **220** surrounding the corresponding conductive layer **222**. If high-k gate dielectric layers **220** surrounding the corresponding conductive layer **222** is over etched too much, slit spacer **229** of slit structure **108** can also be damaged.

[0082] A brief description for the fabrication process of 3D memory device **200** is provided herein. Initially, stack structure **201** including interleaved first dielectric layers **223** and second dielectric layers **225** is formed. Channel structures **110** extending through first dielectric layers **223** and second dielectric layers **225** are formed in core array region **101**. Dummy channel structures **112** can be formed in word line pick-up region **103** of stack structure **201**, in the same process as forming channel structures **110**. DSG layer **224** and stop layer **231** are formed on core array region **101** of stack structure **201**.

[0083] Next, all the second dielectric layers **225** in core array region **101** and parts of the second dielectric layers **225** in word line pick-up region **103** are replaced with conductive layers **222**, for example, by a gate line replacement process through slit openings. High-k gate dielectric layers **220** may be formed prior to the formation of conductive layers **222**, such that conductive layers **222** may be formed surrounded by high-k gate dielectric layers **220**. Slit structures **108** including slit spacers **229** can be formed in the slit openings. Each slit structure **108** may extend vertically through interleaved conductive layers **222** and first dielectric layers **223** of stack structure **201** (as shown in FIG. 2) and laterally across core array region **101** and conductive portion **105** of word line pick-up region **103** (as shown in FIG. 1).

[0084] Subsequently, contact structures **106** extending through first dielectric layers **223** and remainders of second dielectric layers **225** in dielectric portion **107** are formed at different depths, such that contact structures **106** are electrically connected to conductive layers **222**, respectively, in dielectric portion **107**. For example, with reference to FIG. 3A, contact openings **302** extending through first dielectric layers **223** and the remainders of second dielectric layers **225** in dielectric portion **107** are formed at different depths to expose the remainders of second dielectric layers **225** in dielectric portion **107**, respectively. For each contact opening **302**, a contact spacer **204** can be formed on sidewalls and a bottom of contact opening **302**. A part of contact spacer **204** on the bottom of contact opening **302** is removed to expose the respective part of the remainder of a corresponding second dielectric layer **225**. As shown in FIG. 3B, the exposed part of the remainder of the corresponding second dielectric layer **225** is etched by applying a wet etchant through contact opening **302** to form a lateral recess **312**, such that the respective conductive layer **222** in the first portion of stack structure **201** is exposed.

[0085] However, as shown in FIG. 3C which illustrates an enlarged view of a part 314 of FIG. 3B, when the part of the corresponding second dielectric layer 225 is etched away by the wet etchant, high-k gate dielectric layers 220 surrounding the respective conductive layer 222 may also be over etched by the wet etchant. For example, not only a high-k gate dielectric layer 220 on an end surface 317 of the respective conductive layer 222 is etched away, but also high-k gate dielectric layers 220 surrounding the respective conductive layer 222 in spaces 316 and 318 are also etched away, resulting in damage in high-k gate dielectric layers 220 surrounding the respective conductive layer 222. If high-k gate dielectric layers 220 surrounding the respective conductive layer 222 is etched all the way through spaces 316 and 318, slit spacer 229 of slit structure 108 can also be damaged.

[0086] It can be difficult to find an appropriate wet etchant or develop a new wet etchant that can be controlled to only etch the corresponding second dielectric layer 225 (including silicon nitride) without over-etching high-k gate dielectric layers 220 surrounding the respective conductive layer 222. Further, it can also be difficult to control an etching rate and/or etching time to remove only the part of the corresponding second dielectric layer 225 that is enough to expose end surface 317 of the respective conductive layer 222, without over-etching high-k gate dielectric layers 220 in spaces 316 and 318.

[0087] To solve the over-etching issue of high-k gate dielectric layers 220, a high-k dielectric material may be deposited through lateral recess 312 to fill in spaces 316 and 318, so that the damage previously made to high-k gate dielectric layers 220 surrounding the respective conductive layer 222 is repaired. In this case, a new high-k gate dielectric layer is also formed and covers end surface 317 of the respective conductive layer 222 again. Then, the new high-k gate dielectric layer formed on end surface 317 of the respective conductive layer 222 can be removed to expose end surface 317 of the respective conductive layer 222. Subsequently, lateral contact member 206 can be formed in lateral recess 312 in contact with end surface 317 of the respective conductive layer 222; vertical contact member 202 may be formed on a sidewall of contact spacer 204; and filler body 208 may be formed to fill in the remaining space of contact opening 302. In this way, contact structure 106 of FIG. 2 may be formed. However, since (a) additional high-k dielectric material needs to be deposited into spaces 316 and 318 to repair the damage previously made to high-k gate dielectric layers 220 and (b) the new high-k gate dielectric layer formed on end surface 317 of the respective conductive layer 222 needs to be etched back again, the manufacturing process of 3D memory device 200 becomes more complicated, and the cost of 3D memory device 200 can be increased.

[0088] FIG. 4 illustrates cross-sectional side views of a 3D memory device 400 having contact structures 106, according to some aspects of the present disclosure. FIG. 5A illustrates a cross-sectional side view of 3D memory device 400 of FIG. 4, according to some aspects of the present disclosure. FIG. 5B illustrates an enlarged cross-sectional side view of a part 407 of 3D memory device 400 in FIG. 4, according to some aspects of the present disclosure. FIG. 5C illustrates a slit structure 108 in 3D memory device 400 of FIG. 4, according to some aspects of the present disclosure. FIGS. 4 and 5A-5C are described below together.

[0089] 3D memory device 400 can be an example implementation of 3D memory device 100 of FIG. 1. In FIG. 4, one cross-section may be along the BB direction in core array region 101 in FIG. 1, and another cross-section may be along the CC direction in word line pick-up region 103 in FIG. 1. 3D memory device 400 of FIG. 4 may include components and structures like those of 3D memory device 200 of FIG. 2, and the similar description will not be repeated herein.

[0090] In some implementations, 3D memory device 400 may include a semiconductor layer (e.g., substrate 203), stack structure 201 over the semiconductor layer, and a third dielectric layer 412 over stack structure 201 in word line pick-up region 103. Third dielectric layer 412 can include dielectric materials including, but not limited to, silicon oxide, silicon nitride, silicon oxynitride, or any combination thereof.

[0091] Consistent with some aspects of the present disclosure, contact structure **106** of 3D memory device **400** in FIG. **4** may have a structure different from contact structure **106** of 3D memory device **200** in FIG. **2**. As shown in FIG. **4**, contact structure **106** may include a vertical contact member **402** extending in a first direction (e.g., the z-direction), a lateral contact member **406** connecting to vertical contact member **402** and extending in a second direction (e.g., the y-direction), and a spacer **404** surrounding at least a part of vertical contact member **402**. In some implementations, contact structure **106** may further include a filler body **408** surrounded by vertical contact member **402**. A local contact may also be formed on a top surface of filler body **408**. Lateral contact member **406** may connect with a first one of conductive layers **222** (e.g., conductive layer **222a**).

[0092] Contact structure **106** in FIG. **4** may extend through third dielectric layer **412** and a part of the first portion of stack structure **201** to connect with the first one of conductive layers **222**. For example, as illustrated in FIG. **5A**, the cross-section may be along the AA direction in dielectric portion **107** of word line pick-up region **103** in FIG. **1**. Contact structure **106** may include a first contact segment **502** and a second contact segment **504**, which are connected with each other at a first joint region **410** in third dielectric layer **412**. First contact segment **502** may extend through a first part of third dielectric layer **412** in the first direction, and second contact segment **504** may extend through a second part of third dielectric layer **412** and a part of the first portion of stack structure **201** in the first direction. A size **508** of first contact segment **502** can be greater than a size **506** of second contact segment **504** in the second direction perpendicular to the first direction. First contact segment **502** may include a first part of vertical contact member **402** and a first part of filler body **408**. Second contact segment **504** may include spacer **404**, a second part of vertical contact member **402**, and a second part of filler body **408**. The first part and the second part of vertical contact member **402** may connect with each other at first joint region **410** in third dielectric layer **412**. The first part and the second part of filler body **408** may connect with each other at first joint region **410** in third dielectric layer **412**.

[0093] As shown in FIGS. **4** and **5A**, each of first contact segment **502** and second contact segment **504** may have a rectangular shape. In some implementations, each of first contact segment **502** and second contact segment **504** may have any other suitable shape, such as a trapezoidal shape, a square shape, etc., which is not limited herein.

[0094] As shown in FIG. **5A**, different contact structures **106** may extend vertically into stack structure **201** (in dielectric portion **107** of word line pick-up region **103**) at different depths in the z-direction, according to some implementations. The top surfaces of different contact structures **106** can be flush with one another, while the bottom surfaces of different contact structures **106** can extend to different levels, for example, different second dielectric layers **225** of stack structure **201**.

[0095] With reference to FIGS. **4**, second dielectric layers **225** in the first portion of stack structure **201** (in dielectric portion **107** of word line pick-up region **103**) may include: (1) a first one of second dielectric layers **225** (e.g., second dielectric layer **225a**) at a same level as the first one of conductive layers **222** (e.g., conductive layer **222a**) which is connected to lateral contact member **406**; and (2) second ones of second dielectric layers **225** (e.g., second dielectric layers **225b**, **225c**) at the same levels of second ones of conductive layers **222** (e.g., conductive layers **222b**, **222c**), respectively. Lateral contact member **406** is formed in the first one of second dielectric layers **225**. Lateral contact member **406** may protrude into the second portion of stack structure **201** and may connect with the first one of conductive layers **222**.

[0096] With reference to FIG. **5B**, an end surface **590** of each second one of conductive layers **222** can be covered by a first high-k gate dielectric layer **220**, and the second one of conductive layers **222** may connect with a respective second one of second dielectric layers **225** via the first high-k gate dielectric layer **220**. Side surfaces **591** of the first one of conductive layers **222** (e.g., conductive layer **222a**) may be surrounded by second high-k gate dielectric layers **220**. Side surfaces **592** of each second one of conductive layers **222** may be surrounded by third high-k gate

dielectric layers **220**. A first distance **553** from slit structure **108** to the end surface of the first one of conductive layers **222** in the second direction may be smaller than a second distance **555** from slit structure **108** to end surface **590** of the second one of conductive layers **222** in the second direction.

[0097] In some implementations, lateral contact member **406** and the first one of conductive layers **222** may include different materials. For example, lateral contact member **406** and the first one of conductive layers **222** may include Titanium nitride and tungsten, respectively.

[0098] Consistent with some aspects of the present disclosure, slit structure **108** of 3D memory device **400** in FIG. **4** may have a structure different from slit structure **108** of 3D memory device **200** shown in FIG. **2**. For example, with reference to FIGS. **4** and **5C**, slit structure **108** may include a first slit segment **540** and a second slit segment **542**. First slit segment **540** may extend through a part of third dielectric layer **412**, and may include a part of slit spacer **429**. Second slit segment **542** may extend through another part of third dielectric layer **412**, the first portion of stack structure **201**, and a part of substrate **203**. Second slit segment **542** may include another part of slit spacer **429**. First slit segment **540** may connect with second slit segment **542** at a second joint region **418** in third dielectric layer **412**. A size **546** of first slit segment **540** can be greater than a size **544** of second slit segment **542** in the second direction.

[0099] As shown in FIGS. **4** and **5C**, each of first slit segment **540** and second slit segment **542** may have a rectangular shape. In some implementations, each of first slit segment **540** and second slit segment **542** may have any other suitable shape, such as a trapezoidal shape, a square shape, etc., which is not limited herein.

[0100] FIGS. **6A-6R** illustrate a fabrication process for forming a 3D memory device having contact structures, according to some aspects of the present disclosure. Examples of the 3D memory device depicted in FIGS. **6A-6R** include 3D memory devices **100** depicted in FIGS. **1** and 3D memory device **400** depicted in FIGS. **4** and **5A-5C**. By way of example, FIGS. **6A-6R** are described below with reference to 3D memory device **400**.

[0101] As illustrated in FIG. **6A**, stack structure **201** including multiple pairs of a first dielectric layer **223** and a second dielectric layer **225** (a.k.a., a stack sacrificial layer) is formed above a substrate **203** (e.g., a silicon substrate). Stack structure **201** includes vertically interleaved first dielectric layers **223** and second dielectric layers **225**, according to some implementations. First and second dielectric layers **223** and **225** can be alternately deposited above substrate **203** to form stack structure **201**. In some implementations, each first dielectric layer **223** includes a layer of silicon oxide, and each second dielectric layer **225** includes a layer of silicon nitride. Stack structure **201** can be formed by one or more thin film deposition processes including, but not limited to, chemical vapor deposition (CVD), physical vapor deposition (PVD), atomic layer deposition (ALD), or any combination thereof.

[0102] A plurality of channel openings **610** are formed in core array region **101**, such that each channel opening **610** becomes the location for growing an individual channel structure **110** as shown in FIG. **6B**. Each channel opening **610** extends vertically through stack structure **201** in core array region **101**. In some implementations, fabrication processes for forming channel openings **610** include wet etching and/or dry etching, such as deep-ion reactive etching (DRIE). A plurality of dummy channel openings **612**, which extend vertically through stack structure **201** can be formed in word line pick-up region **103** simultaneously as channel openings **610** by the same wet etching and/or dry etching, such as DRIE.

[0103] As illustrated in FIG. **6B**, channel structures **110** can be formed in core array region **101** of stack structure **201**. For each channel opening **610**, a memory layer (including a blocking layer, a storage layer, and a tunneling layer) and a channel layer are sequentially formed in this order along sidewalls and the bottom surface of the channel opening. In some implementations, the memory layer is first deposited along the sidewalls and bottom surface of the channel opening, and the semiconductor channel is then deposited over the memory layer. The blocking layer, storage layer,

and tunneling layer can be subsequently deposited in this order using one or more thin film deposition processes, such as ALD, CVD, PVD, any other suitable processes, or any combination thereof, to form the memory layer. The channel layer can then be formed by depositing a semiconductor material, such as polysilicon, over the tunneling layer of the memory layer using one or more thin film deposition processes, such as ALD, CVD, PVD, any other suitable processes, or any combination thereof. In some implementations, a first silicon oxide layer, a silicon nitride layer, a second silicon oxide layer, and a polysilicon layer (a “SONO” structure) are subsequently deposited to form the memory layer and the channel layer of channel structure **110**.

[0104] In some implementations, as illustrated in FIG. 6B, dummy channel structures **112** can be formed in word line pick-up region **103** of stack structure **201**, in the same process of forming channel structures **110**. For example, dummy channel structures **112** can be formed simultaneously as channel structures **110** by the same thin film deposition processes that deposit a memory layer (including a blocking layer, a storage layer, and a tunneling layer) and a channel layer into the dummy channel openings. It is understood that in some examples, dummy channel structures **112** may be formed in a separate process from channel structures **110**.

[0105] As illustrated in FIG. 6C, a first slit opening **620** extending through first dielectric layers **223** and second dielectric layers **225** and across core array region **101** and word line pick-up region **103** of stack structure **201** is formed. First slit opening **620** can be an opening that extends vertically through first dielectric layers **223** and second dielectric layers **225** of stack structure **201** until substrate **203**. First slit opening **620** can also extend laterally across core array region **101** and word line pick-up region **103** in the x-direction (the word line direction), for example, corresponding to slit structure **108** in FIG. 1. In some implementations, fabrication processes for forming first slit opening **620** include wet etching and/or dry etching, such as DRIE, of first dielectric layers **223** and second dielectric layers **225**. The etching process through stack structure **201** may not stop at the top surface of substrate **203** and may continue to etch part of substrate **203** to ensure that first slit opening **620** extends vertically all the way through all first dielectric layers **223** and second dielectric layers **225** of stack structure **201**.

[0106] In FIG. 6D, first slit opening **620** can be filled with a preliminary slit structure **621** (e.g., a sacrificial layer). For example, first slit opening **620** in core array region **101** and word line pick-up region **103** can be covered by the sacrificial layer. In some implementations, the sacrificial layer that is different from first dielectric layers **223** and second dielectric layers **225**, such as a polysilicon layer or a carbon layer, is deposited into first slit opening using one or more thin film deposition processes, such as CVD, PVD, ALD, or any combination thereof, to fill first slit opening **620**. A chemical mechanical polishing (CMP) process may be performed on the sacrificial layer.

[0107] In FIG. 6E, a first dielectric sub-layer **623** may be deposited over stack structure **201** to cover preliminary slit structure **621**. First dielectric sub-layer **623** can be formed by one or more thin film deposition processes including, but not limited to, chemical vapor deposition (CVD), physical vapor deposition (PVD), atomic layer deposition (ALD), or any combination thereof. First dielectric sub-layer **623** can include dielectric materials including, but not limited to, silicon oxide, silicon nitride, silicon oxynitride, or any combination thereof.

[0108] A first contact opening **622** extending through first dielectric sub-layer **623** and a part of the first portion of stack structure **201** (e.g., in dielectric portion **107** of word line pick-up region **103**) can be formed. In some implementations, fabrication processes for forming first contact opening **622** include wet etching and/or dry etching, such as DRIE, of first dielectric sub-layer **623**, first dielectric layers **223**, and second dielectric layers **225**.

[0109] In FIG. 6F, a spacer **404** can be formed by depositing a first dielectric material on a sidewall of first contact opening **622**. For example, spacer **404** can be formed on the sidewall and the bottom surface of first contact opening **622**, thereby covering first dielectric layers **223** and second dielectric layers **225** exposed from the sidewall of first contact opening **622**. In some implementations, spacer **404** is formed by depositing dielectric materials, such as silicon oxide,

using one or more thin film deposition processes, such as ALD, CVD, PVD, any other suitable processes, or any combination thereof, over the sidewall and the bottom surface of first contact opening **622**. A part of spacer **404** on the bottom of first contact opening **622** is removed to expose a part of a first one of second dielectric layers **225** in dielectric portion **107** of word line pick-up region **103**. In some implementations, the etching rate, direction, and/or duration of RIE are controlled to etch only the part of spacer **404** on the bottom surface, but not on the sidewall, of first contact opening **622**, i.e., “punching” through spacer **404** in the z-direction to expose only the first one of second dielectric layers **225** from the bottom, but not other second dielectric layers **225** from the sidewall.

[0110] In FIG. **6G**, a lateral recess **625** is formed below the bottom of first contact opening **622** by removing a part of the first one of second dielectric layers **225** exposed at the bottom of first contact opening **622**. For example, the part of the first one of second dielectric layers **225** exposed from the bottom of first contact opening **622** is removed by wet etching to form lateral recess **625**, leaving the remainder of the first one of second dielectric layers **225** at the same level, as well as other second dielectric layers **225** at other levels, in dielectric portion **107** of word line pick-up region **103** intact. In some implementations, the part of the first one of second dielectric layers **225** is wet etched by applying a wet etchant through first contact opening **622**, creating lateral recess **625** sandwiched between two first dielectric layers **223**. The wet etchant can include phosphoric acid for etching the first one of second dielectric layers **225** including silicon nitride. In some implementations, the etching rate and/or etching time are controlled to remove only part of the first one of second dielectric layers **225**. By controlling the etching time, the wet etchant does not travel all the way to completely remove the first one of second dielectric layers **225** in dielectric portion **107** of word line pick-up region **103**. Since the sidewall of first contact opening **622** is still covered by spacer **404** (e.g., silicon oxide) that is resistant to the etchant for removing the part of the first one of second dielectric layers **225** (e.g., silicon nitride), second dielectric layers **225** at other levels remain intact in dielectric portion **107**.

[0111] In FIG. **6H**, first contact opening **622** and lateral recess **625** are filled with a second dielectric material (e.g., a sacrificial layer) different from that of first dielectric layers **223** and second dielectric layers **225**. In some implementations, the second dielectric material, such as polysilicon, can be deposited in lateral recess **625** and first contact opening **622** using one or more thin film deposition processes, such as ALD, CVD, PVD, any other suitable processes, or any combination thereof. A CMP process may be performed on the second dielectric material filled in first contact opening **622**.

[0112] In FIG. **6I**, a second dielectric sub-layer **627** is deposited over first dielectric sub-layer **623** to cover the second dielectric material filled in first contact opening **622**. Second dielectric sub-layer **627** can be formed by one or more thin film deposition processes including, but not limited to, chemical vapor deposition (CVD), physical vapor deposition (PVD), atomic layer deposition (ALD), or any combination thereof. Second dielectric sub-layer **627** can include dielectric materials including, but not limited to, silicon oxide, silicon nitride, silicon oxynitride, or any combination thereof.

[0113] Subsequently, with reference to FIGS. **6J-6L**, a gate line replacement process may be performed to replace parts of second dielectric layers **225** in the second portion of stack structure **201** with conductive layers **222**. For example, all the second dielectric layers **225** in core array region **101** and parts of second dielectric layers **225** in conductive portion **105** of word line pick-up region **103** are replaced with conductive layers **222**, for example, by the gate line replacement process.

[0114] In FIG. **6J**, a second slit opening **628** can be formed to expose preliminary slit structure **621**. Second slit opening **628** can be an opening that extends vertically through first dielectric sub-layers **623** and second dielectric sub-layers **627** to expose the top surface of preliminary slit structure **621**. A size of second slit opening **628** may be greater than a size of first slit opening **620** in the y

direction. Second slit opening **628** can also extend laterally across core array region **101** and word line pick-up region **103** in the x-direction (the word line direction), for example, corresponding to slit structure **108** in FIG. 1. In some implementations, fabrication processes for forming second slit opening **628** include wet etching and/or dry etching, such as DRIE, of first dielectric sub-layers **623** and second dielectric sub-layers **627**.

[0115] In FIG. 6K, preliminary slit structure **621** (shown in FIGS. 6D-6J) can be removed to expose first slit opening **620**. For example, first slit opening **620** is re-opened by removing the sacrificial layer of preliminary slit structure **621** to expose first dielectric layers **223** and second dielectric layers **225**. In some implementations, the sacrificial layer is etched away from first slit opening **620**, for example, using potassium hydroxide (KOH) for etching the sacrificial layer having polysilicon, to open first slit opening **620**.

[0116] Next, the parts of second dielectric layers **225** in the second portion of stack structure **201** are removed through first slit opening **620** to form a plurality of lateral openings **629**, **630**. The plurality of lateral openings **629** are in core array region **101**. The plurality of lateral openings **630** are in conductive portion **105** of word line pick-up region **103**.

[0117] For example, all second dielectric layers **225** (as shown in FIG. 6J) in core array region **101** are fully removed by wet etching to form lateral openings **629**. In some implementations, second dielectric layers **225** are wet etched by applying a wet etchant through first slit opening **620**. The wet etchant can include phosphoric acid for etching second dielectric layers **225** including silicon nitride. In some implementations, the etching rate and/or etching time are controlled to ensure that all second dielectric layers **225** in core array region **101** are completely etched away.

[0118] Further, parts of second dielectric layers **225** in conductive portion **105** of word line pick-up region **103** are removed by wet etching to form lateral openings **630**, leaving the remainders of second dielectric layers **225** in dielectric portion **107** of word line pick-up region **103** intact. By controlling the etching time, the wet etchant does not travel all the way to completely remove second dielectric layers **225** in word line pick-up region **103**, thereby defining two portions in word line pick-up region **103**—conductive portion **106** in which second dielectric layers **225** are removed, and dielectric portion **107** in which second dielectric layers **225** remain. It is noted that since lateral recess **625** (shown in FIG. 6G) is filled with dielectric material, such as polysilicon, which is resistant to the wet etchant, a size of a lateral opening **630a** in the same level as the first one of second dielectric layers **225** can be shorter than that of other lateral openings **630** in other levels of second dielectric layers **225** in the y-direction (e.g., the length of lateral opening **630a** in the y-direction < a length of a lateral opening **630b** in the y-direction).

[0119] In FIG. 6L, high-k gate dielectric layers **220** are formed on walls of the plurality of lateral openings **629**, **630**. Then, the plurality of lateral openings **629**, **630** are filled with a first conductive material to form conductive layers **222** such that end surfaces and side surfaces of conductive layers **222** are surrounded by high-k gate dielectric layers **220**, respectively. For example, conductive layers **222** are deposited into lateral recesses **629** and **630** in core array region **101** and conductive portion **105** of word line pick-up region **103** through first slit opening **620** and second slit opening **628**. High-k gate dielectric layers **220** are deposited into lateral recesses **629** and **630** prior to conductive layers **222**, such that conductive layers **222** are deposited on and surrounded by high-k gate dielectric layers **220**. Conductive layers **222**, such as metal layers, can be deposited using one or more thin film deposition processes, such as ALD, CVD, PVD, any other suitable processes, or any combination thereof.

[0120] In FIG. 6M, slit structure **108** is formed to fill first slit opening **620** and second slit opening **628**. A third dielectric sub-layer **631** is deposited over second dielectric sub-layer **627** to cover slit structure **108** formed in first and second slit openings **620**, **628**. Third dielectric layer **412** of FIG. 4 may include first, second and third dielectric sub-layer **623**, **627**, **631**. With combined reference to FIGS. 5C, 6L, and 6M, first slit segment **540** of slit structure **108** may be formed in second slit opening **628**. Second slit segment **542** of slit structure **108** may be formed in first slit opening **620**.

In one example, second joint region **418** may include a region where first slit segment **540** connects with second slit segment **542**. In another example, second joint region **418** may include a region where first slit opening **620** connects with second slit opening **628** in third dielectric layer **412**. [0121] In some implementations, first and second slit openings **620** and **628** are formed using a chopping process, respectively, which employs two different masks so that first and second slit openings **620** and **628** can reach different depths inside stack structure **201** and have different opening widths in the y direction. However, sidewall shoulders (such as sidewall shoulders **699** in FIG. **6L**) are easy to be created in the openings as a result of multiple times of etching with masks having a gap or overlay therebetween. Slit structure **108** (e.g., first slit segment **540** of slit structure) may have slit shoulders **698** as shown in FIG. **6M**. Slit shoulders **698** may rest on sidewall shoulders **699** (shown in FIG. **6L**). Second joint region **418** may include a region where sidewall shoulders **699** of FIG. **6L** are located, and slit shoulders **698** are formed above second joint region **418**.

[0122] Stop layer **231** can be formed on core array region **101** of stack structure **201**, using one or more thin film deposition processes including, but not limited to, CVD, PVD, ALD, or any combination thereof. DSG channel structures **227** can be formed extending vertically through stop layer **231** to be in contact with the upper ends of channel structures **110**. Channel contacts **226** can be formed in stop layer **231**.

[0123] In FIG. **6N**, a second contact opening **634** is formed in third dielectric layer **412** to expose the second dielectric material filled in first contact opening **622**. In some implementations, fabrication processes for forming second contact opening **634** include wet etching and/or dry etching, such as DRIE, of third dielectric layer **412**.

[0124] In FIG. **6O**, the second dielectric material filled in lateral recess **625** and first contact opening **622** is removed through second contact opening **634** to expose lateral recess **625** and a sidewall of spacer **404**. A size of second contact opening **634** is greater than a size of first contact opening **622** in the y-direction. In some implementations, the second dielectric material is etched away from first contact opening **622** and lateral recess **625**, for example, using potassium hydroxide (KOH) to re-open first contact opening **622** and lateral recess **625**.

[0125] In FIG. **6P**, a high-k gate dielectric layer **220a** (shown in FIG. **6O**) on an end surface **636** of the first one of conductive layers **222** is removed to expose end surface **636** of the first one of conductive layers **222**. For example, high-k gate dielectric layer **220a** can be etched, for example, using wet etching, to expose end surface **636** of the first one of conductive layers **222**.

[0126] In FIG. **6Q**, a second conductive material is deposited to fill lateral recess **625** to form lateral contact member **406**. The second conductive material is also deposited on the sidewall of spacer **404** and on a sidewall of second contact opening **634** to form vertical contact member **402**. Lateral contact member **406** and vertical contact member **402** can be deposited using one or more thin film deposition processes, such as ALD, CVD, PVD, any other suitable processes, or any combination thereof. Lateral contact member **406** connects with end surface **636** of the first one of conductive layers **222**.

[0127] With combined reference to FIGS. **5A**, **6O**, **6Q**, and **6R**, first contact segment **502** of contact structure **106** may be formed in second contact opening **634**. Second contact segment **504** of contact structure **106** may be formed in first contact opening **622**. In one example, first joint region **410** may include a region where first contact segment **502** connects with second contact segment **504**. In another example, first joint region **410** may include a region where first contact opening **622** connects with second contact opening **634** in third dielectric layer **412**.

[0128] In some implementations, first and second contact openings **622** and **634** are formed using a chopping process, respectively, which employs two different masks so that first and second contact openings **622** and **634** can reach different depths inside stack structure **201** and have different opening widths in the y direction. However, sidewall shoulders (such as sidewall shoulders **697** in FIG. **6O**) are easy to be created in the openings as a result of multiple times of etching with masks

having a gap or overlay therebetween. Contact structure **106** (e.g., first contact segment **502** of contact structure **106**) may include contact shoulders **696** as shown in FIG. **6Q**. For example, contact shoulders **696** can be a part of vertical contact member **402** and can be in first contact segment **502**. Contact shoulders **696** may rest on sidewall shoulders **697** (shown in FIG. **6O**). First joint region **410** may include a region where sidewall shoulders **697** of FIG. **6O** are located, and contact shoulders **696** are formed above first joint region **410**.

[0129] In FIG. **6R**, a remaining space of first contact opening **622** and a remaining space of second contact opening **634** are filled with a third dielectric material to form filler body **408**. A contact pad **650** can be formed on the top surface of filler body **408**. For example, the third dielectric material can be deposited using one or more thin film deposition processes, such as ALD, CVD, PVD, any other suitable processes, or any combination thereof, to form filler body **408**.

[0130] As described above with reference to FIG. **6H**, the second dielectric material (such as polysilicon) can be filled in lateral recess **625**, so that the first one of second dielectric layers **225** (including silicon nitride) interfaces polysilicon directly. As a result, the removal of the first one of second dielectric layers **225** in conductive portion **105** can be easily controlled to be stopped at the polysilicon interface, as shown in FIG. **6K**. After conductive layers **222** are filled in lateral openings **630**, polysilicon in lateral recess **625** interfaces high-k gate dielectric layer **222a** on end surface **636** of the first one of conductive layers **222**, as shown in FIG. **6L** (unlike FIG. **3A** in which it is silicon nitride that interfaces the high-k gate dielectric layers). As a result, the removal of polysilicon in lateral recess **625** can be easily stopped at high-k gate dielectric layer **220a**, as shown in FIG. **6O** (e.g., high-k gate dielectric layer **220a** is resistant to the wet etchant used to etch the polysilicon). Compared to FIGS. **3B-3C**, the etching process in FIG. **6O** can be easily controlled, and no damage is made to the high-k gate dielectric layers. That is, the over etching issue of the high-k gate dielectric layers can be avoided. As a result, the manufacture cost of the memory device can be reduced.

[0131] FIG. **7** illustrates a flowchart of a method **700** for forming an example 3D memory device having contact structures, according to some aspects of the present disclosure. Examples of the 3D memory device include 3D memory devices **100** depicted in FIG. **1** or 3D memory device **200** depicted in FIGS. **4**, **5A-5C**, and **6A-6R**. It is understood that the operations shown in method **700** are not exhaustive and that other operations can be performed as well before, after, or between any of the illustrated operations. Further, some of the operations may be performed simultaneously, or in a different order than that shown in FIG. **7**.

[0132] Referring to FIG. **7**, method **700** starts at operation **702**, in which a stack structure is formed over a semiconductor layer. The stack structure includes alternating first dielectric layers and second dielectric layers. The semiconductor layer can be, for example, a substrate.

[0133] Method **700** proceeds to operation **704**, as illustrated in FIG. **7**, in which a third dielectric layer is formed over the stack structure.

[0134] Method **700** proceeds to operation **706**, as illustrated in FIG. **7**, in which a contact structure extending through the third dielectric layer and a part of the stack structure is formed. The contact structure includes a first contact segment and a second contact segment which are connected with each other at a first joint region in the third dielectric layer.

[0135] Consistent with some aspects of the present disclosure, operations **704** and **706** may be performed together. For example, during the process of forming the contact structure, the third dielectric layer can also be formed, as illustrated above with reference to FIGS. **6E-6R**.

[0136] In some implementations, with reference to FIGS. **6C-6D** and **7**, prior to forming the contact structure, method **700** may include forming a first slit opening **620** extending through the stack structure and a part of the semiconductor layer, and filling first slit opening **620** with a preliminary slit structure **621**. Then, forming third dielectric layer **412** at operation **704** may include depositing a first dielectric sub-layer **623** over the stack structure to cover preliminary slit structure **621**, as illustrated in FIG. **6E**. Third dielectric layer **412** may include first dielectric sub-layer **623**.

[0137] In some implementations, to form the contact structure at operation **706**, method **700** may include forming a first contact opening **622** extending through first dielectric sub-layer **623** and a part of a first portion of the stack structure, as illustrated in FIG. **6E**. Method **700** may also include forming a spacer **404** by depositing a first dielectric material on a sidewall of first contact opening **622**, as illustrated in FIG. **6F**. Method **700** may also include forming a lateral recess **625** below a bottom of first contact opening **622** by removing a part of a first one of the second dielectric layers **225** exposed at the bottom of first contact opening **622**, as illustrated in FIG. **6G**. Method **700** may also include filling first contact opening **622** and lateral recess **625** with a second dielectric material different from that of the first dielectric layers and the second dielectric layers, as illustrated in FIG. **6H**.

[0138] In some implementations, to form the third dielectric layer at operation **704**, method **700** may also include depositing a second dielectric sub-layer **627** over first dielectric sub-layer **623** to cover the second dielectric material filled in the first contact opening, as illustrated in FIG. **6I**. The third dielectric layer further includes second dielectric sub-layer **627**.

[0139] In some implementations, method **700** may further include performing a gate line replacement process to replace parts of the second dielectric layers in a second portion of the stack structure with conductive layers. For example, method **700** may include forming a second slit opening **628** to expose preliminary slit structure **621**, as illustrated in FIG. **6J**. Method **700** may also include (a) removing preliminary slit structure **621** to expose first slit opening **620** through second slit opening **628** and (b) removing the parts of the second dielectric layers in the second portion of the stack structure through first slit opening **620** to form a plurality of lateral openings, **629**, **930**, as illustrated in FIG. **6K**. Method **700** may also include (a) forming high-k gate dielectric layers **220** on walls of the plurality of lateral openings **629**, **630**, and (b) filling the plurality of lateral openings **629**, **630** with a first conductive material to form conductive layers **222**, such that end surfaces and side surfaces of conductive layers **222** are surrounded by high-k gate dielectric layers **220**, respectively, as illustrated in FIG. **6L**. Method **700** may also include forming a slit structure **108** to fill first slit opening **620** and second slit opening **628**, as illustrated in FIG. **6M**.

[0140] In some implementations, to form the third dielectric layer at operation **704**, method **700** may further include depositing a third dielectric sub-layer **631** over second dielectric sub-layer **627** to cover slit structure **108** formed in the first and second slit openings, as illustrated in FIG. **6M**. The third dielectric layer may further include third dielectric sub-layer **631**.

[0141] In some implementations, to form the contact structure at operation **706**, method **700** may also include forming a second contact opening **634** in the third dielectric layer **412** to expose the second dielectric material filled in first contact opening **622**, as illustrated in FIG. **6N**. A size of second contact opening **634** is greater than a size of first contact opening **622** in the y-direction. Method **700** may also include removing the second dielectric material through second contact opening **634** to expose lateral recess **625** and a sidewall of spacer **404**, as illustrated in FIG. **6O**. Method **700** may further include removing the first corresponding high-k gate dielectric layer **220a** on end surface **636** of the first one of the conductive layers to expose the end surface **636** of the first one of the conductive layers, as illustrated in FIG. **6P**. Method **700** may further include (a) depositing a second conductive material to fill lateral recess **625** to form a lateral contact member **406** and (b) depositing the second conductive material on the sidewall of spacer **404** and on a sidewall of second contact opening **634** to form a vertical contact member **402**, as illustrated in FIG. **6Q**. Method **700** may further include filling a remaining space of first contact opening **622** and a remaining space of second contact opening **634** with a third dielectric material to form a filler body **408**, as illustrated in FIG. **6R**.

[0142] FIG. **8** illustrates a block diagram of an example system **800** having a 3D memory device, according to some aspects of the present disclosure. System **800** can be a mobile phone, a desktop computer, a laptop computer, a tablet, a vehicle computer, a gaming console, a printer, a positioning device, a wearable electronic device, a smart sensor, a virtual reality (VR) device, an argument

reality (AR) device, or any other suitable electronic devices having storage therein. As shown in FIG. 8, system **800** can include a host **808** and a memory system **802** having one or more 3D memory devices **804** and a memory controller **806**. Host **808** can be a processor of an electronic device, such as a central processing unit (CPU), or a system-on-chip (SoC), such as an application processor (AP). Host **808** can be configured to send or receive data to or from 3D memory devices **804**.

[0143] 3D memory device **804** can be any 3D memory device disclosed herein, such as 3D memory device **100** depicted in FIGS. 1 and 3D memory device **400** depicted in FIGS. 4, 5A-5C, and 6A-6R.

[0144] Memory controller **806** (a.k.a., a controller circuit) is coupled to 3D memory device **804** and host **808** and is configured to control 3D memory device **804**, according to some implementations. For example, memory controller **806** may be configured to operate the plurality of channel structures via the word lines. Memory controller **806** can manage the data stored in 3D memory device **804** and communicate with host **808**. In some implementations, memory controller **806** is designed for operating in a low duty-cycle environment like secure digital (SD) cards, compact Flash (CF) cards, universal serial bus (USB) Flash drives, or other media for use in electronic devices, such as personal computers, digital cameras, mobile phones, etc. In some implementations, memory controller **806** is designed for operating in a high duty-cycle environment SSDs or embedded multi-media-cards (eMMCs) used as data storage for mobile devices, such as smartphones, tablets, laptop computers, etc., and enterprise storage arrays. Memory controller **806** can be configured to control operations of 3D memory device **804**, such as read, erase, and program operations. Memory controller **806** can also be configured to manage various functions with respect to the data stored or to be stored in 3D memory device **804** including, but not limited to bad-block management, garbage collection, logical-to-physical address conversion, wear leveling, etc. In some implementations, memory controller **806** is further configured to process error correction codes (ECCs) with respect to the data read from or written to 3D memory device **804**. Any other suitable functions may be performed by memory controller **806** as well, for example, formatting 3D memory device **804**. Memory controller **806** can communicate with an external device (e.g., host **808**) according to a particular communication protocol. For example, memory controller **806** may communicate with the external device through at least one of various interface protocols, such as a USB protocol, an MMC protocol, a peripheral component interconnection (PCI) protocol, a PCI-express (PCI-E) protocol, an advanced technology attachment (ATA) protocol, a serial-ATA protocol, a parallel-ATA protocol, a small computer small interface (SCSI) protocol, an enhanced small disk interface (ESDI) protocol, an integrated drive electronics (IDE) protocol, a Firewire protocol, etc.

[0145] Memory controller **806** and one or more 3D memory devices **804** can be integrated into various types of storage devices, for example, be included in the same package, such as a universal Flash storage (UFS) package or an eMMC package. That is, memory system **802** can be implemented and packaged into different types of end electronic products. In one example as shown in FIG. 9A, memory controller **806** and a single 3D memory device **804** may be integrated into a memory card **902**. Memory card **902** can include a PC card (PCMCIA, personal computer memory card international association), a CF card, a smart media (SM) card, a memory stick, a multimedia card (MMC, RS-MMC, MMCmicro), an SD card (SD, miniSD, microSD, SDHC), a UFS, etc. Memory card **902** can further include a memory card connector **904** electrically coupling memory card **902** with a host (e.g., host **808** in FIG. 8). In another example as shown in FIG. 9B, memory controller **806** and multiple 3D memory devices **804** may be integrated into an SSD **906**. SSD **906** can further include an SSD connector **908** electrically coupling SSD **906** with a host (e.g., host **808** in FIG. 8). In some implementations, the storage capacity and/or the operation speed of SSD **906** is greater than those of memory card **902**.

[0146] The foregoing description of the specific implementations can be readily modified and/or

adapted for various applications. Therefore, such adaptations and modifications are intended to be within the meaning and range of equivalents of the disclosed implementations, based on the teaching and guidance presented herein.

[0147] The breadth and scope of the present disclosure should not be limited by any of the above-described example implementations, but should be defined only in accordance with the following claims and their equivalents.

Claims

1. A memory device, comprising: a semiconductor layer; a stack structure over the semiconductor layer and comprising alternating first layers and first dielectric layers, wherein the first layers in a first portion of the stack structure comprise second dielectric layers, and the first layers in a second portion adjacent to the first portion of the stack structure comprise conductive layers; a third dielectric layer over the stack structure; and a contact structure extending through the third dielectric layer and a part of the first portion of the stack structure to be connected with a first one of the conductive layers, wherein the contact structure comprises a first contact segment and a second contact segment which are connected with each other at a first joint region in the third dielectric layer.
2. The memory device of claim 1, wherein: the first contact segment extends through a first part of the third dielectric layer in a first direction; the second contact segment extends through a second part of the third dielectric layer and the part of the stack structure in the first direction; and a size of the first contact segment is greater than a size of the second contact segment in a second direction perpendicular to the first direction.
3. The memory device of claim 1, wherein: the contact structure comprises a vertical contact member extending in a first direction and a lateral contact member connecting to the vertical contact member and extending in a second direction; the lateral contact member connects with the first one of the conductive layers; the first contact segment comprises a first part of the vertical contact member; the second contact segment comprises a second part of the vertical contact member; and the first part and the second part of the vertical contact member connect with each other at the first joint region in the third dielectric layer.
4. The memory device of claim 3, wherein: the second dielectric layers in the first portion of the stack structure comprise: a first one of the second dielectric layers at a same level as the first one of the conductive layers; and a second one of the second dielectric layers at a same level as a second one of the conductive layers; an end surface of the second one of the conductive layers is covered by a first high dielectric constant (high-k) gate dielectric layer, and the second one of the conductive layers connects with the second one of the second dielectric layers via the first high-k gate dielectric layer; and the lateral contact member of the contact structure protrudes into the second portion of the stack structure and connects with the first one of the conductive layers.
5. The memory device of claim 4, wherein: side surfaces of the first one of the conductive layers are surrounded by second high-k gate dielectric layers; and side surfaces of the second one of the conductive layers are surrounded by third high-k gate dielectric layers.
6. The memory device of claim 3, wherein the lateral contact member and the first one of the conductive layers comprise Titanium nitride and tungsten, respectively.
7. The memory device of claim 4, further comprising: a slit structure comprising a first slit segment and a second slit segment, wherein the first slit segment extends through a third part of the third dielectric layer, wherein the second slit segment extends through a fourth part of the third dielectric layer, the first portion of the stack structure, and a part of the semiconductor layer, wherein the first slit segment connects with the second slit segment at a second joint region in the third dielectric layer, wherein a first distance from the slit structure to an end surface of the first one of the conductive layers in the second direction is smaller than a second distance from the slit structure to

the end surface of the second one of the conductive layers in the second direction, and wherein a size of the first slit segment is greater than a size of the second slit segment in the second direction.

8. A method for forming a memory device, comprising: forming a stack structure over a semiconductor layer, wherein the stack structure comprises alternating first dielectric layers and second dielectric layers; forming a third dielectric layer over the stack structure; and forming a contact structure extending through the third dielectric layer and a part of the stack structure, wherein the contact structure comprises a first contact segment and a second contact segment which are connected with each other at a first joint region in the third dielectric layer.

9. The method of claim 8, wherein forming the contact structure comprises: forming a spacer; forming a vertical contact member extending in a first direction and a lateral contact member extending in a second direction perpendicular to the first direction, wherein the vertical contact member connects with the lateral contact member, and at least a part of the vertical contact member is surrounded by the spacer; and forming a filler body, wherein the filler body is surrounded by the vertical contact member.

10. The method of claim 9, wherein prior to forming the contact structure, the method further comprises: forming a first slit opening extending through the stack structure and a part of the semiconductor layer; and filling the first slit opening with a preliminary slit structure, wherein forming the third dielectric layer comprises depositing a first dielectric sub-layer over the stack structure to cover the preliminary slit structure, wherein the third dielectric layer comprises the first dielectric sub-layer, wherein forming the contact structure further comprises forming a first contact opening extending through the first dielectric sub-layer and the part of the stack structure, and wherein forming the spacer comprises depositing a first dielectric material on a sidewall of the first contact opening.

11. The method of claim 10, wherein forming the vertical contact member and the lateral contact member comprises: forming a lateral recess below a bottom of the first contact opening by removing a part of a first one of the second dielectric layers exposed at the bottom of the first contact opening; and filling the first contact opening and the lateral recess with a second dielectric material different from that of the first dielectric layers and the second dielectric layers, wherein forming the third dielectric layer further comprises: depositing a second dielectric sub-layer over the first dielectric sub-layer to cover the second dielectric material filled in the first contact opening, wherein the third dielectric layer further comprises the second dielectric sub-layer.

12. The method of claim 11, wherein: the stack structure comprises a first portion and a second portion adjacent to the first portion, and the contact structure extends through the third dielectric layer and a part of the first portion of the stack structure; and the method further comprises: performing a gate line replacement process to replace parts of the second dielectric layers in the second portion of the stack structure with conductive layers.

13. The method of claim 12, wherein performing the gate line replacement process comprises: forming a second slit opening to expose the preliminary slit structure; removing the preliminary slit structure to expose the first slit opening through the second slit opening; removing the parts of the second dielectric layers in the second portion of the stack structure through the first slit opening to form a plurality of lateral openings; forming high dielectric constant (high-k) gate dielectric layers on walls of the plurality of lateral openings, and filling the plurality of lateral openings with a first conductive material to form the conductive layers such that end surfaces and side surfaces of the conductive layers are surrounded by the high-k gate dielectric layers, respectively; and forming a slit structure to fill the first slit opening and the second slit opening.

14. The method of claim 13, wherein: the lateral recess filled with the first dielectric material protrudes into the second portion of the stack structure and connects with a first corresponding high-k gate dielectric layer on an end surface of a first one of the conductive layers; a second one of the second dielectric layers in the first portion of the stack structure connects with a second corresponding high-k gate dielectric layer at an end surface of a second one of the conductive

layers; and forming the third dielectric layer further comprises depositing a third dielectric sub-layer over the second dielectric sub-layer to cover the slit structure formed in the first and second slit openings, wherein the third dielectric layer further comprises the third dielectric sub-layer.

15. The method of claim 14, wherein forming the vertical contact member and the lateral contact member further comprises: forming a second contact opening in the third dielectric layer to expose the second dielectric material filled in the first contact opening, wherein a size of the second contact opening is greater than a size of the first contact opening in the second direction; removing the second dielectric material through the second contact opening to expose the lateral recess and a sidewall of the spacer; removing the first corresponding high-k gate dielectric layer on the end surface of the first one of the conductive layers to expose the end surface of the first one of the conductive layers; and depositing a second conductive material to fill the lateral recess, on the sidewall of the spacer, and on a sidewall of the second contact opening to form the lateral contact member and the vertical contact member, respectively.

16. The method of claim 15, wherein: the lateral contact member of the contact structure protrudes into the second portion of the stack structure and connects with the first one of the conductive layers; and the first joint region comprises a region where the first contact opening connects with the second contact opening in the third dielectric layer.

17. The method of claim 15, wherein forming the filler body comprises: filling a remaining space of the first contact opening and a remaining space of the second contact opening with a third dielectric material.

18. The method of claim 14, wherein: the slit structure comprises a first slit segment filling the first slit opening and a second slit segment filling the second slit opening; the first slit segment connects with the second slit segment at a second joint region in the third dielectric layer; a size of the first slit segment is greater than a size of the second slit segment in the second direction; and a first distance from the slit structure to the end surface of the first one of the conductive layers in the second direction is smaller than a second distance from the slit structure to the end surface of the second one of the conductive layers in the second direction.

19. The method of claim 9, wherein: the first contact segment comprises a first part of the vertical contact member and a first part of the filler body; the second contact segment comprises a second part of the vertical contact member and a second part of the filler body; the first part and the second part of the vertical contact member connect with each other at the first joint region in the third dielectric layer; the first part and the second part of the filler body connect with each other at the first joint region in the third dielectric layer; and a size of the first contact segment is greater than a size of the second contact segment in the second direction perpendicular to the first direction.

20. A system, comprising: a memory device, comprising: a semiconductor layer; a stack structure over the semiconductor layer and comprising alternating first layers and first dielectric layers, wherein the first layers in a first portion of the stack structure comprise second dielectric layers, and the first layers in a second portion adjacent to the first portion of the stack structure comprise conductive layers; a third dielectric layer over the stack structure; and a contact structure extending through the third dielectric layer and a part of the first portion of the stack structure to be connected with a first one of the conductive layers, wherein the contact structure comprises a first contact segment and a second contact segment that are connected with each other at a first joint region in the third dielectric layer; and a memory controller coupled to the memory device and configured to control an operation of the memory device.
