

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12389246
Kind Code	B2
Date of Patent	August 12, 2025
Inventor(s)	Yang; Yu et al.

Method and apparatus for determining measurement target based on configuration information, device, and medium

Abstract

Embodiments of the present disclosure provide a method and an apparatus for determining a measurement target, a device, and a medium. The method for determining a measurement target, applied to a terminal device, includes: receiving configuration information from a network side device, where the configuration information includes that a parameter reportQuantity of a Channel State Information (CSI) report is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes a Signal to Interference plus Noise Ratio (SINR) or a Reference Signal Received Power (RSRP); and determining the measurement target according to the configuration information.

Inventors:	Yang; Yu (Dongguan, CN), Sun; Peng (Dongguan, CN)
Applicant:	VIVO MOBILE COMMUNICATION CO., LTD. (Dongguan, CN)
Family ID:	76039223
Assignee:	VIVO MOBILE COMMUNICATION CO., LTD. (Dongguan, CN)
Appl. No.:	17/723434
Filed:	April 18, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20220248243 A1	Aug. 04, 2022

Foreign Application Priority Data

CN	201911207265.8	Nov. 29, 2019
----	----------------	---------------

Related U.S. Application Data

Publication Classification

Int. Cl.: **H04W24/08** (20090101); **H04B7/06** (20060101); **H04B17/309** (20150101); **H04W24/10** (20090101)

U.S. Cl.:

CPC **H04W24/08** (20130101); **H04B7/0626** (20130101); **H04B17/309** (20150115); **H04W24/10** (20130101);

Field of Classification Search

CPC: H04W (24/08); H04W (24/10); H04B (17/309); H04B (7/0626)

References Cited**U.S. PATENT DOCUMENTS**

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
11881905	12/2023	Onggosanusi	N/A	H04L 5/005
2015/0208269	12/2014	Damnjanovic et al.	N/A	N/A
2017/0332267	12/2016	Kim et al.	N/A	N/A
2019/0058517	12/2018	Kang et al.	N/A	N/A
2019/0165847	12/2018	Kim et al.	N/A	N/A
2019/0306924	12/2018	Zhang et al.	N/A	N/A
2021/0337415	12/2020	Chen	N/A	H04L 5/005
2021/0368468	12/2020	Xing	N/A	H04W 64/00
2022/0014957	12/2021	Guo	N/A	H04W 72/21

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
108282212	12/2017	CN	N/A
109392000	12/2018	CN	N/A
109644364	12/2018	CN	N/A
110035447	12/2018	CN	N/A
2018127149	12/2017	WO	N/A

OTHER PUBLICATIONS

Extended European Search Report issued in related European Application No. 20892539.6, mailed Dec. 6, 2022, 14 pages. cited by applicant

Ericsson, "Draft CR on CPU occupancy rules for CSI-ReportConfig with higher layer paramter reportQunatity set to none" Nov. 2018, 3GPP TSG-RAN WG1 Meeting#95, R1-1814225, 2 pages. cited by applicant

International Search Report issued in corresponding International Application No. PCT/CN2020/131212, mailed Feb. 19, 2021, 4 pages. cited by applicant

VIVO, "Remaining issues on multi-beam transmission", 3GPP TSG RAN WG1 #99, R1-1912040, Nov. 22, 2019 cited by applicant

First Office Action issued in related Chinese Application No. 201911207265.8, mailed Dec. 30,

2021, 10 pages. cited by applicant

Office Action issued in related European Application No. 20892539.6, mailed Nov. 29, 2024, 8 pages. cited by applicant

Apple Inc., "Feature Lead Summary 3 on SCell BFR and L1-SINR", 3GPP TSG-RAN WG Meeting #98bis, R1-1911549, Oct. 2019, 23 pages. cited by applicant

Primary Examiner: Patel; Chandrahas B

Attorney, Agent or Firm: IPX PLLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of International Application No. PCT/CN2020/131212, filed Nov. 24, 2020, which claims priority to Chinese Patent Application No. 201911207265.8, filed Nov. 29, 2019. The entire contents of each of the above-referenced applications are expressly incorporated herein by reference.

TECHNICAL FIELD

(1) Embodiments of the present disclosure relate to the field of communications technologies, and in particular to a method and an apparatus for determining a measurement target, a device, and a medium.

BACKGROUND

(2) During beam measurement and selection, a commonly used parameter to measure beam quality is a Reference Signal Received Power (RSRP). To further improve accuracy of beam measurement and selection, especially in multi-cell, multi-user, and multi-beam scenes, it is necessary to measure a Signal to Interference plus Noise Ratio (SINR).

(3) At present, for a Channel State Information (CSI) report, it is stipulated that when a parameter reportQuantity is set to a synchronization signal block-index-SINR (ssb-Index-SINR) or a channel state information-reference signal resource indicator-SINR (cri-SINR), a terminal device needs to perform SINR measurement.

(4) However, a measurement target is not stipulated when the parameter reportQuantity is set to null.

SUMMARY

(5) According to a first aspect, an embodiment of the present disclosure provides a method for determining a measurement target, applied to a terminal device, and including: receiving configuration information from a network side device, where the configuration information includes that a parameter reportQuantity of a CSI report is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement; and determining the measurement target according to the configuration information.

(6) According to a second aspect, an embodiment of the present disclosure provides a method for determining a measurement target, applied to a network side device, including: sending configuration information to a terminal device, where the configuration information includes that a parameter reportQuantity of a CSI report is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement.

(7) According to a third aspect, an embodiment of the present disclosure provides an apparatus for determining a measurement target, applied to a terminal device, and including: a receiving module, configured to receive configuration information from a network side device, where the

configuration information includes that a parameter reportQuantity of a CSI report is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement; and a first determining module, configured to determine the measurement target according to the configuration information.

(8) According to a fourth aspect, an embodiment of the present disclosure provides an apparatus for determining a measurement target, applied to a network side device, including: a sending module, configured to send configuration information to a terminal device, where the configuration information includes that a parameter reportQuantity is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement.

(9) According to a fifth aspect, an embodiment of the present disclosure provides a terminal device, including: a memory, a processor, and a computer program that is stored in the memory and that can be run on the processor, where when the processor executes the computer program, the method for determining a measurement target according to the first aspect of the present disclosure is implemented.

(10) According to a sixth aspect, an embodiment of the present disclosure provides a network side device, including: a memory, a processor, and a computer program that is stored in the memory and that can be run on the processor, where when the processor executes the computer program, the method for determining a measurement target according to the second aspect of the present disclosure is implemented.

(11) According to a seventh aspect, an embodiment of the present disclosure provides a computer-readable storage medium, where the computer-readable storage medium stores a computer program, and when the computer program is executed by a processor, the method for determining a measurement target according to the first aspect or the second aspect of embodiments of the present disclosure is implemented.

Description

BRIEF DESCRIPTION OF DRAWINGS

(1) To describe the technical solutions in the embodiments of the present disclosure more clearly, the following briefly describes the accompanying drawings required to be used in the embodiments of the present disclosure. A person of ordinary skill in the art may still derive other drawings from these accompanying drawings.

(2) FIG. 1 is a schematic flow chart of a method for determining a measurement target, applied to a terminal device, according to an embodiment of the present disclosure;

(3) FIG. 2 is an exemplary schematic diagram of an aperiodic CSI report trigger timing sequence according to an embodiment of the present disclosure;

(4) FIG. 3 is a schematic structural diagram of an apparatus for determining a measurement target, applied to a terminal device, according to an embodiment of the present disclosure;

(5) FIG. 4 is a schematic diagram of a hardware structure of an example of a terminal device according to an embodiment of the present disclosure; and

(6) FIG. 5 is a schematic diagram of a hardware structure of a network side device according to an embodiment of the present disclosure.

DETAILED DESCRIPTION

(7) The following describes the technical solutions in the embodiments of the present disclosure with reference to the accompanying drawings. Apparently, the described embodiments are some rather than all of the embodiments of the present disclosure. All other embodiments obtained by a person of ordinary skill in the art based on the embodiments of the present disclosure shall fall

within the protection scope of the present disclosure.

(8) FIG. 1 is a schematic flow chart of a method for determining a measurement target, applied to a terminal device, according to an embodiment of the present disclosure. As shown in FIG. 1, the method for determining a measurement target, applied to a terminal device, may include the following steps.

(9) **S101**: Receive configuration information from a network side device, where the configuration information includes that a parameter reportQuantity of a CSI report is set to null (null), and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement.

(10) **S102**: Determine the measurement target according to the configuration information.

(11) In this embodiment of the present disclosure, the SINR may refer to a L1-SINR and the RSRP may refer to a L1-RSRP.

(12) The network side device according to this embodiment of the present disclosure may be a base station, where the base station may be a frequently used base station, or an evolved node base station (eNB), or a device such as a network side device (for example, a next generation node base station (gNB) or a Transmission and Reception Point (TRP)) or a cell in the 5G system, or a network side device in a subsequent evolution communications system. In some embodiments, the terminal device may be a mobile phone, a tablet computer, a smart watch, a smart home appliance, or the like, which is not limited in this embodiment of the present disclosure.

(13) In an embodiment of the present disclosure, the configuration information may include any one of the following:

(14) a plurality of Reference Signal (RS) resource settings; at least one RS resource setting used for channel measurement and at least one RS resource setting used for interference measurement; at least one Channel Measurement Resource (CMR) setting and at least one Interference Measurement Resource (IMR) setting; or CMR information and IMR information.

(15) In this case, the terminal device determines that the measurement target is SINR measurement, and then performs the SINR measurement.

(16) In an embodiment of the present disclosure, the configuration information may include any one of the following: one RS resource setting; one RS resource setting used for RSRP measurement; one CMR setting; or CMR information.

(17) In this case, the terminal device determines that the measurement target is the RSRP measurement, and then performs the RSRP measurement.

(18) In an embodiment of the present disclosure, when the measurement target is the SINR measurement, the configuration information is further used to indicate that a quantity ratio of the CMR to the IMR included in the RS resource is a preset ratio. In this case, the terminal device may determine, according to the configuration information, that the quantity ratio of the CMR to the IMR is the preset ratio.

(19) In an embodiment of the present disclosure, when the measurement target is the SINR measurement, the terminal device may further determine the time occupied by a CSI processing unit required for the CSI report including a SINR measurement result.

(20) In an embodiment of the present disclosure, if the CSI report including the SINR measurement result is a semi-persistent CSI report, the time occupied by the CSI processing unit required for the CSI report including the SINR measurement result is from a first symbol to a second symbol.

(21) The first symbol is a 1.sup.st symbol in the earliest transmission occasion of a first RS resource and a second RS resource used for SINR calculation.

(22) The second symbol is a Z.sub.i'.sup.th symbol after the last symbol of the latest RS resource in the transmission occasion of the first RS resource and the second RS resource used for the SINR calculation.

(23) The first RS resource is a periodic or semi-persistent channel state information-reference signal (CSI-RS) resource or a Synchronization Signal and PBCH block (SSB) resource used for

channel measurement.

(24) The second RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

(25) That is, the time occupied by the CSI processing unit required for the semi-persistent CSI report is: from the first symbol used for SINR calculation, in the earliest transmission occasion of the periodic or semi-persistent CSI-RS resource or SSB resource used for channel measurement and a periodic or semi-persistent CSI-RS resource or SSB resource used for interference measurement, to a $Z_{i'}^{\text{sup.th}}$ symbol used for SINR calculation after the last symbol of the latest RS resource in a transmission occasion of the periodic or semi-persistent CSI-RS resource or SSB resource used for channel measurement and the periodic or semi-persistent CSI-RS resource or SSB resource used for interference measurement.

(26) In an embodiment of the present disclosure, the value of i may be 1.

(27) In an embodiment of the present disclosure, if the CSI report including the SINR measurement result is an aperiodic CSI report, the time occupied by the CSI processing unit required for the CSI report is from a third symbol to a fourth symbol.

(28) The third symbol is a $1^{\text{sup.st}}$ symbol after a physical downlink control channel (PDCCH) configured to trigger the CSI report.

(29) The fourth symbol is the last symbol between a $Z_{j'}^{\text{sup.th}}$ symbol and a $Z_j^{\text{sup.th}}$ symbol.

(30) The $Z_j^{\text{sup.th}}$ symbol is a $Z_j^{\text{sup.th}}$ symbol after the first symbol after the PDCCH configured to trigger the CSI report.

(31) The $Z_{j'}^{\text{sup.th}}$ symbol is a $Z_{j'}^{\text{sup.th}}$ symbol after the last symbol of the latest RS resource between a third RS resource and a fourth RS resource used for the SINR calculation.

(32) The third RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the channel measurement.

(33) The fourth RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

(34) That is, the time occupied by the CSI processing unit required for the aperiodic CSI report is: from the first symbol after a PDCCH configured to trigger a CSI report to the last symbol between the $Z_j^{\text{sup.th}}$ symbol after the first symbol after the PDCCH configured to trigger the CSI report and the $Z_{j'}^{\text{sup.th}}$ symbol, used for SINR calculation, after the last symbol of the latest RS resource in the periodic or semi-persistent CSI-RS resource or SSB resource used for channel measurement and in the periodic or semi-persistent CSI-RS resource or SSB resource used for interference measure.

(35) In an embodiment of the present disclosure, the value of j may be 1.

(36) In an embodiment of the present disclosure, when the measurement target is SINR measurement, a configuration parameter of a channel state information-reference signal resource set (CSI-RS resource set) (such as a CMR resource set) used for channel measurement in the configuration information does not include a tracking reference signal information (trs-info) parameter, and/or a configuration parameter of the CSI-RS resource set (such as an IMR resource set) used for interference measurement in the configuration information does not include the trs-info parameter.

(37) In an embodiment of the present disclosure, when the measurement target is the RSRP measurement, the terminal device may further determine the time occupied by a CSI processing unit required for a CSI report including a RSRP measurement result.

(38) In an embodiment of the present disclosure, if the CSI report including the RSRP measurement result is a semi-persistent CSI report, the time occupied by the CSI processing unit required for the CSI report including the RSRP measurement result is from a fifth symbol to a sixth symbol.

(39) The fifth symbol is a $1^{\text{sup.st}}$ symbol in the earliest transmission occasion of a fifth RS

resource used for RSRP calculation.

(40) The sixth symbol is a $Z_{\text{sub}.3' \text{sup}.th}$ symbol after the last symbol of the latest RS resource in the transmission occasion in the fifth RS resource used for the RSRP calculation.

(41) The fifth RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the RSRP measurement.

(42) That is, the time occupied by the CSI processing unit required for the semi-persistent CSI report is: from the first symbol used for RSRP calculation in the earliest transmission occasion of the periodic or semi-persistent CSI-RS resource or SSB resource used for RSRP measurement to a $Z_{\text{sub}.3'}$ symbol used for RSRP calculation after the last symbol of the latest RS resource in the transmission occasion of the periodic or semi-persistent CSI-RS resource or SSB resource used for RSRP measurement.

(43) In an embodiment of the present disclosure, if the CSI report including the RSRP measurement result is an aperiodic CSI report, the time occupied by the CSI processing unit required for the CSI report including the RSRP measurement result is from a seventh symbol to an eighth symbol.

(44) The seventh symbol is a $1_{\text{sup}.st}$ symbol after a PDCCH configured to trigger the CSI report.

(45) The eighth symbol is the last symbol between the $Z_{\text{sub}.3 \text{sup}.th}$ symbol and the $Z_{\text{sub}.3' \text{sup}.th}$ symbol.

(46) The $Z_{\text{sub}.3 \text{sup}.th}$ symbol is a $Z_{\text{sub}.3 \text{sup}.th}$ symbol from the first symbol after the PDCCH configured to trigger the CSI report.

(47) The $Z_{\text{sub}.3' \text{sup}.th}$ symbol is a $Z_{\text{sub}.3' \text{sup}.th}$ symbol after the last symbol of the latest resource in the CSI-RS resource or SSB resource used for the RSRP measurement.

(48) That is, the time occupied by the CSI processing unit required for the aperiodic CSI report is: from the first symbol after the PDCCH configured to trigger the CSI report to the last symbol between the $Z_{\text{sub}.3 \text{sup}.th}$ symbol after the first symbol after the PDCCH configured to trigger the CSI report and the $Z_{\text{sub}.3' \text{sup}.th}$ symbol after the last symbol of the latest resource in the CSI-RS resource or SSB resource used for RSRP measurement.

(49) In an embodiment of the present disclosure, when the measurement target is the RSRP measurement, a configuration parameter of the CSI-RS resource set used for channel measurement in the configuration information does not include a trs-info parameter.

(50) A value of (Z, Z') will be described below with reference to FIG. 2. FIG. 2 is an exemplary schematic diagram of an aperiodic CSI report trigger timing sequence according to an embodiment of the present disclosure.

(51) When a CSI request field (CSI request field) in Downlink Control Information (DCI) triggers one or more CSI reports transmitted through a Physical Uplink Shared Channel (PUSCH), a terminal device needs to provide effective CSI reports when the following conditions are met:

(52) If timing advance is considered, a first uplink symbol for transmission of a CSI report is not earlier than a symbol $Z_{\text{sub}.ref}$ and not earlier than a symbol $Z_{\text{sub}.ref}'$. $Z_{\text{sub}.ref}$ is defined as a next uplink symbol, namely a start time of a Cyclic prefix (CP) is at T seconds after the last symbol of a PDCCH configured to trigger the CSI report.

(53) When a triggered CSI report n is based on an aperiodic CSI-RS, $Z_{\text{sub}.ref}'$ is defined as a next uplink symbol, namely a start time of the CP is at T' seconds after the last symbol of an aperiodic CSI-RS used for channel measurement, an aperiodic CSI interference measurement (CSI-IM) for interference measurement, and an aperiodic Non-Zero Power (NZP) CSI-RS used for interference measurement.

(54) Z and Z' are defined as

$$(55) Z = \max_{m=0, \dots, M-1} (Z(m)) \text{ and } Z' = \max_{m=0, \dots, M-1} (Z'(m)),$$

where M is the number of updated CSI reports, and (Z(m), Z'(m)) corresponds to the time occupied by a CSI processing unit corresponding to an m^{sup}.th updated CSI report.

(56) In the prior art, conditions under which a value of (Z, Z') is a value of (Z.sub.1, Z.sub.1') are as follows: (1) when L=0 processing units are occupied and CSI to be transmitted is a single piece of CSI and the CSI corresponds to wideband frequency-granularity, the CSI is triggered without a transmission block and/or a PUSCH of hybrid automatic repeat request acknowledgment, where the CSI corresponds to at most 4 CSI-RS ports in a single resource, and there is no CRI report, a CodebookType parameter is set to "typeI-SinglePane" or a parameter reportQuantity is set to "cri-RI-CQI"; and (2) the CSI to be transmitted corresponds to the broadband frequency-granularity, where the CSI corresponds to at most 4 CSI-RS ports in a single resource, and there is no CRI report, the CodebookType parameter is set to the typeI-SinglePane or the parameter reportQuantity is set to the cri-RI-CQI.

(57) A condition in which a value of (Z, Z') is a value of (Z.sub.3, Z.sub.3') is as follows: the reportQuantity is set to cri-RSRP or ssb-Index-RSRP.

(58) A condition that a value of (Z, Z') is a value of (Z.sub.2, Z.sub.2') is as follows: a condition other than conditions for the foregoing two groups of values.

(59) According to the foregoing description of the values of Z and Z', it can be seen that in the prior art, values of the Z and Z' are not defined in SINR measurement. For the Z.sub.i'.sup.th, Z.sub.j.sup.th, Z.sub.j'.sup.th symbols mentioned in the time occupied by the CSI processing unit during the SINR measurement in this embodiment of the present disclosure, values of i and j may both be 1, that is, the value of (Z, Z') is (Z.sub.1, Z.sub.1') during the SINR measurement.

(60) In other words, when the measurement target determined by the terminal device according to the configuration information provided in this embodiment of the present disclosure is the SINR measurement, the value of (Z, Z') may also be determined as (Z.sub.1, Z.sub.1'). That is, the following condition needs to be added to the conditions under which the value of (Z, Z') is (Z.sub.1, Z.sub.1'): the reportQuantity is set to null, and at least one RS resource setting used for channel measurement and at least one RS resource setting used for interference measurement are configured.

(61) An embodiment of the present disclosure further provides a method for determining a measurement target, applied to a network side device. The method for determining a measurement target, applied to a network side device, may include the following step.

(62) Send configuration information to a terminal device, where the configuration information includes that a parameter reportQuantity of a CSI report is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement.

(63) In an embodiment of the present disclosure, the configuration information may include any one of the following: a plurality of RS resource settings; at least one RS resource setting used for channel measurement and at least one RS resource setting used for interference measurement; at least one CMR setting and at least one IMR setting; or CMR information and IMR information.

(64) In an embodiment of the present disclosure, the configuration information is further used to indicate that a quantity ratio of the CMR to the IMR included in the RS resource is a preset ratio.

(65) In an embodiment of the present disclosure, the time occupied by the CSI processing unit required for the CSI report may further be determined by the network side device; and a CSI report includes an SINR measurement result.

(66) In an embodiment of the present disclosure, the CSI report is a semi-persistent CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a first symbol to a second symbol.

(67) The first symbol is a 1.sup.st symbol in the earliest transmission occasion of a first RS resource and a second RS resource used for SINR calculation.

(68) The second symbol is a Z.sub.i'.sup.th symbol after the last symbol of the latest RS resource in a transmission occasion of the first RS resource and the second RS resource used for the SINR calculation.

- (69) The first RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for channel measurement.
- (70) The second RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.
- (71) In an embodiment of the present disclosure, the CSI report is an aperiodic CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a third symbol to a fourth symbol.
- (72) The third symbol is a 1.sup.st symbol after a PDCCH configured to trigger the CSI report.
- (73) The fourth symbol is the last symbol between a Z.sub.j.sup.th symbol and a Z.sub.i'.sup.th symbol.
- (74) The Z.sub.j.sup.th symbol is a Z.sub.j.sup.th symbol after the first symbol after the PDCCH is configured to trigger the CSI report.
- (75) The Z.sub.j'.sup.th symbol is a Z.sub.j'.sup.th symbol after the last symbol of the latest RS resource between a third RS resource and a fourth RS resource used for the SINR calculation.
- (76) The third RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the channel measurement.
- (77) The fourth RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.
- (78) In an embodiment of the present disclosure, a configuration parameter of a CSI-RS resource set used for channel measurement in the configuration information does not include a trs-info parameter, and/or a configuration parameter of a CSI-RS resource set used for interference measurement in the configuration information does not include the trs-info parameter.
- (79) In an embodiment of the present disclosure, the configuration information may include any one of the following:
- (80) one RS resource setting; one RS resource setting used for RSRP measurement; one CMR setting; or CMR information.
- (81) In an embodiment of the present disclosure, the time occupied by the CSI processing unit required for the CSI report may further be determined by the network side device. The CSI report includes an RSRP measurement result.
- (82) In an embodiment of the present disclosure, if the CSI report including the RSRP measurement result is a semi-persistent CSI report, the time occupied by the CSI processing unit required for the CSI report including the RSRP measurement result is from a fifth symbol to a sixth symbol.
- (83) The fifth symbol is a 1.sup.st symbol in the earliest transmission occasion of a fifth RS resource used for RSRP calculation.
- (84) The sixth symbol is a Z.sub.3'.sup.th symbol after the last symbol of the latest RS resource in the transmission occasion in the fifth RS resource used for the RSRP calculation.
- (85) The fifth RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the RSRP measurement.
- (86) In an embodiment of the present disclosure, if the CSI report including the RSRP measurement result is an aperiodic CSI report, the time occupied by the CSI processing unit required for the CSI report including the RSRP measurement result is from a seventh symbol to an eighth symbol.
- (87) The seventh symbol is a 1.sup.st symbol after a PDCCH configured to trigger the CSI report.
- (88) The eighth symbol is the last symbol between the Z.sub.3.sup.th symbol and the Z.sub.3'.sup.th symbol.
- (89) The Z.sub.3.sup.th symbol is a Z.sub.3.sup.th symbol from the first symbol after the PDCCH configured to trigger the CSI report.
- (90) The Z.sub.3'.sup.th symbol is a Z.sub.3'.sup.th symbol after the last symbol of the latest resource in the CSI-RS resource or SSB resource used for the RSRP measurement.

(91) In an embodiment of the present disclosure, a configuration parameter of the CSI-RS resource set in the configuration information does not include a trs-info parameter.

(92) It can be understood that the symbols in this embodiment of the present disclosure may be Orthogonal Frequency Division Multiplexing (OFDM) symbols.

(93) An embodiment of the present disclosure further provides an apparatus for determining a measurement target, applied to a terminal device. FIG. 3 is a schematic structural diagram of an apparatus for determining a measurement target, applied to a terminal device, according to an embodiment of the present disclosure. As shown in FIG. 3, the apparatus 300 for determining a measurement target, applied to a terminal device, may include: a receiving module 301, configured to receive configuration information from a network side device, where the configuration information includes that a parameter reportQuantity of a CSI report is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement; and a first determining module 302, configured to determine the measurement target according to the configuration information.

(94) In an embodiment of the present disclosure, the configuration information may include any one of the following: a plurality of RS resource settings; at least one RS resource setting used for channel measurement and at least one RS resource setting used for interference measurement; at least one CMR setting and at least one IMR setting; or CMR information and IMR information.

(95) The first determining module 302 may be specifically configured to determine that the measurement target is the SINR measurement.

(96) In an embodiment of the present disclosure, the apparatus 300 for determining a measurement target, applied to a terminal device, may further include: a second determining module, configured to determine, according to the configuration information, that a quantity ratio of the CMR to the IMR is a preset ratio.

(97) In an embodiment of the present disclosure, the apparatus 300 for determining a measurement target, applied to a terminal device, may further include: a third determining module, configured to determine the time occupied by a CSI processing unit required for the CSI report. The CSI report includes a SINR measurement result.

(98) In an embodiment of the present disclosure, the CSI report is a semi-persistent CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a first symbol to a second symbol.

(99) The first symbol is a 1.sup.st symbol in the earliest transmission occasion of a first RS resource and a second RS resource used for SINR calculation.

(100) The second symbol is a Z.sub.i'.sup.th symbol after the last symbol of the latest RS resource in a transmission occasion of the first RS resource and the second RS resource used for the SINR calculation.

(101) The first RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for channel measurement.

(102) The second RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

(103) In an embodiment of the present disclosure, the CSI report is an aperiodic CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a third symbol to a fourth symbol.

(104) The third symbol is a 1.sup.st symbol after a physical downlink control channel PDCCH configured to trigger the CSI report.

(105) The fourth symbol is the last symbol between a Z.sub.j.sup.th symbol and a Z.sub.j'.sup.th symbol.

(106) The Z.sub.j.sup.th symbol is a Z.sub.j.sup.th symbol after the first symbol after the PDCCH configured to trigger the CSI report.

(107) The $Z_{j'}^{th}$ symbol is a $Z_{j'}^{th}$ symbol after the last symbol of the latest RS resource between a third RS resource and a fourth RS resource used for the SINR calculation.

(108) The third RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the channel measurement.

(109) The fourth RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

(110) In an embodiment of the present disclosure, a configuration parameter of a CSI-RS resource set used for channel measurement in the configuration information does not include a `trs-info` parameter, and/or a configuration parameter of a CSI-RS resource set used for interference measurement in the configuration information does not include the `trs-info` parameter.

(111) In an embodiment of the present disclosure, the configuration information may include any one of the following: one RS resource setting; one RS resource setting used for RSRP measurement; one CMR setting; or CMR information.

(112) The first determining module **302** may be specifically configured to determine that the measurement target is the RSRP measurement.

(113) In an embodiment of the present disclosure, a configuration parameter of the CSI-RS resource set in the configuration information does not include a `trs-info` parameter.

(114) An embodiment of the present disclosure further provides an apparatus for determining a measurement target, applied to a network side device. The apparatus for determining a measurement target, applied to a network side device, may include: a sending module, configured to send configuration information to a terminal device, where the configuration information includes that a `parameterReportQuantity` is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement.

(115) In an embodiment of the present disclosure, the configuration information may include any one of the following: a plurality of RS resource settings; at least one RS resource setting used for channel measurement and at least one RS resource setting used for interference measurement; at least one CMR setting and at least one IMR setting; or CMR information and IMR information.

(116) In an embodiment of the present disclosure, the configuration information is further used to indicate that a quantity ratio of the CMR to the IMR included in the RS resource is a preset ratio.

(117) In an embodiment of the present disclosure, the apparatus for determining a measurement target, applied to a network side device, may further include: a determining module, configured to determine the time occupied by a CSI processing unit required for a CSI report, where the CSI report includes a SINR measurement result.

(118) In an embodiment of the present disclosure, the CSI report is a semi-persistent CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a first symbol to a second symbol.

(119) The first symbol is a 1^{st} symbol in the earliest transmission occasion of a first RS resource and a second RS resource used for SINR calculation.

(120) The second symbol is a $Z_{i'}^{th}$ symbol after the last symbol of the latest RS resource in a transmission occasion of the first RS resource and the second RS resource used for the SINR calculation.

(121) The first RS resource is a periodic or semi-persistent channel state information-reference signal CSI-RS resource or a synchronization signal block SSB resource used for the channel measurement.

(122) The second RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

(123) In an embodiment of the present disclosure, the CSI report is an aperiodic CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a third symbol to a fourth symbol.

(124) The third symbol is a 1.sup.st symbol after a physical downlink control channel PDCCH configured to trigger the CSI report.

(125) The fourth symbol is the last symbol between a Z.sub.j.sup.th symbol and a Z.sub.j'.sup.th symbol.

(126) The Z.sub.j.sup.th symbol is a Z.sub.j.sup.th symbol after the first symbol after the PDCCH configured to trigger the CSI report.

(127) The Z.sub.j'.sup.th symbol is a Z.sub.j'.sup.th symbol after the last symbol of the latest RS resource between a third RS resource and a fourth RS resource used for the SINR calculation.

(128) The third RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the channel measurement.

(129) The fourth RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

(130) In an embodiment of the present disclosure, a configuration parameter of a CSI-RS resource set used for channel measurement in the configuration information does not include a trs-info parameter, and/or a configuration parameter of a CSI-RS resource set used for interference measurement in the configuration information does not include the trs-info parameter.

(131) In an embodiment of the present disclosure, the configuration information may include any one of the following: one RS resource setting; one RS resource setting used for RSRP measurement; one CMR setting; or CMR information.

(132) In an embodiment of the present disclosure, a configuration parameter of the CSI-RS resource set in the configuration information does not include a trs-info parameter.

(133) An embodiment of the present disclosure further provides a terminal device, including a processor, a memory, and a computer program that is stored in the memory and that can be run on the processor. When the computer program is executed by the processor, processes of the foregoing embodiments of the method for determining a measurement target, applied to a terminal device, are implemented, and a same technical effect can be achieved. To avoid repetition, details are not described herein.

(134) FIG. 4 is a schematic diagram of a hardware structure of an example of a terminal device according to an embodiment of the present disclosure. The terminal device **400** includes, but is not limited to: a radio frequency unit **401**, a network module **402**, an audio output unit **403**, an input unit **404**, a sensor **405**, a display unit **406**, a user input unit **407**, an interface unit **408**, a memory **409**, a processor **410**, a power supply **411**, and the like. It can be understood by a person skilled in the art that, a structure of the terminal device shown in FIG. 4 does not constitute any limitation on the terminal device, and the terminal device may include more or fewer components than those shown in the figure, or combine some components, or have different component arrangements. In this embodiment of the present disclosure, the terminal device includes but is not limited to a mobile phone, a tablet computer, a laptop computer, a palmtop computer, an in-vehicle terminal, a wearable device, a pedometer, and the like.

(135) The radio frequency unit **401** is configured to receive configuration information from a network side device, where the configuration information includes that a parameter reportQuantity of a CSI report is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement; and

(136) The memory **409** may be configured to store a software program and various kinds of data. The memory **409** may mainly include a program storage area and a data storage area. The program storage area may store an operating system, an application required by at least one function (for example, a sound play function or an image display function), and the like. The data storage area may store data (for example, audio data or an address book) or the like created based on use of the mobile phone. In addition, the memory **409** may include a high-speed random access memory, and may further include a non-volatile memory such as at least one magnetic disk storage device, a

flash memory device, or another volatile solid-state storage device.

(137) The processor **410** is a control center of the terminal device, is connected to each part of the entire terminal device by using various interfaces and lines, and performs various functions of the terminal device and data processing by running or executing the software program and/or a module that are/is stored in the memory **409** and invoking data stored in the memory **409**, to perform overall monitoring on the terminal device. The processor **410** may include one or more processing units. In some embodiments, an application processor and a modem processor may be integrated into the processor **410**. The application processor mainly processes an operating system, a user interface, an application, and the like. The modem processor mainly processes wireless communication. It may be understood that, alternatively, the modem processor may not be integrated into the processor **410**.

(138) According to this embodiment, the processor **410** can run a computer program that is stored in the memory **409** to implement various processes of the method for determining a measurement target, applied to a terminal device. For example, the processor **410** is configured to determine the measurement target according to the configuration information.

(139) According to this embodiment of the present disclosure, when the parameter reportQuantity is set to null, the measurement target can be determined, and then corresponding measurement can be performed.

(140) It should be understood that in this embodiment of the present disclosure, the radio frequency unit **401** may be configured to receive and transmit information, or receive and transmit signals during a call. Specifically, the radio frequency unit receives downlink data from a base station, and transmits the downlink data to the processor **410** for processing; and transmits uplink data to the base station. Generally, the radio frequency unit **401** includes but is not limited to an antenna, at least one amplifier, a transceiver, a coupler, a low noise amplifier, a duplexer, and the like. In addition, the radio frequency unit **401** may further communicate with another device by using a wireless communications system and network.

(141) The terminal device provides wireless broadband Internet access for the user by using the network module **402**, for example, helping the user send and receive an e-mail, browse a web page, and access streaming media.

(142) The audio output unit **403** may convert audio data received by the radio frequency unit **401** or the network module **402** or stored in the memory **409** into an audio signal, and output the audio signal into sound. In addition, the audio output unit **403** may further provide an audio output (for example, call signal receiving sound or message receiving sound) related to a specific function performed by the terminal device **400**. The audio output unit **403** includes a loudspeaker, a buzzer, a receiver, and the like.

(143) The input unit **404** is configured to receive an audio signal or a video signal. The input unit **404** may include a graphics processing unit (GPU) **4041** and a microphone **4042**. The graphics processing unit **4041** processes image data of a static image or video obtained by an image capture apparatus (such as, a camera) in a video capture mode or an image capture mode. A processed image frame may be displayed on the display unit **406**. The image frame processed by the graphics processing unit **4041** may be stored in the memory **409** (or another storage medium) or sent by using the radio frequency unit **401** or the network module **402**. The microphone **4042** may receive a sound and can process such a sound into audio data. Processed audio data may be converted, in a call mode, into a format that can be sent to a mobile communication base station by using the radio frequency unit **401** for output.

(144) The terminal device **400** further includes at least one sensor **405**, such as an optical sensor, a motion sensor, and other sensors. Specifically, the light sensor includes an ambient light sensor and a proximity sensor. The ambient light sensor may adjust luminance of the display panel **4061** based on brightness of ambient light. The proximity sensor may turn off the display panel **4061** and/or backlight when the terminal device **400** moves to an ear. As a type of the motion sensor, an

accelerometer sensor may detect an acceleration value in each direction (generally, three axes), and detect a value and a direction of gravity when the accelerometer sensor is static, and may be used in an application for recognizing a posture of the terminal device (such as screen switching between landscape and portrait modes, a related game, or magnetometer posture calibration), a function related to vibration recognition (such as a pedometer or a knock), and the like. The sensor **405** may further include a fingerprint sensor, a pressure sensor, an iris sensor, a molecular sensor, a gyroscope, a barometer, a hygrometer, a thermometer, an infrared sensor, and the like. Details are not described herein.

(145) The display unit **406** is configured to display information entered by a user or information provided for a user. The display unit **406** may include a display panel **4061**, and the display panel **4061** may be configured in a form of Liquid Crystal Display (LCD), Organic Light-Emitting Diode (OLED), or the like.

(146) The user input unit **407** may be configured to receive input digit or character information, and generate a key signal input related to a user setting and function control of the terminal device. Specifically, the user input unit **407** includes a touch panel **4071** and another input device **4072**. The touch panel **4071** is also referred to as a touchscreen, and may collect a touch operation performed by the user on or near the touch panel **4071** (for example, an operation performed on or near the touch panel **4071** by the user by using any appropriate object or accessory such as a finger or a stylus). The touch panel **4071** may include two parts: a touch detection apparatus and a touch controller. The touch detection apparatus detects a touch position of a user, detects a signal brought by a touch operation, and transmits the signal to the touch controller. The touch controller receives touch information from the touch detection apparatus, converts the touch information into contact coordinates, sends the contact coordinates to the processor **410**, and receives and executes a command from the processor **410**. In addition, the touch panel **4071** may be implemented by various types, such as a resistive type, a capacitive type, an infrared type, a surface acoustic wave type, or the like. In addition to the touch panel **4071**, the user input unit **407** may further include another input device **4072**. Specifically, the another input device **4072** may include but is not limited to a physical keyboard, a function key (for example, a volume control key, an on/off key), a trackball, a mouse, and a joystick. Details are not described herein again.

(147) Further, the touch panel **4071** may cover the display panel **4061**. After detecting the touch operation on or near the touch panel **4071**, the touch panel transmits the touch operation to the processor **410** to determine a type of a touch event, and then the processor **410** provides corresponding visual output on the display panel **4061** based on the type of the touch event. In FIG. 4, although the touch panel **4071** and the display panel **4061** are used as two independent parts to implement input and output functions of the terminal device, in some embodiments, the touch panel **4071** and the display panel **4061** may be integrated to implement the input and output functions of the terminal device. This is not specifically limited herein.

(148) The interface unit **408** is an interface for connecting an external apparatus with the terminal device **400**. For example, the external apparatus may include a wired or wireless headset jack, an external power supply (or a battery charger) port, a wired or wireless data port, a storage card port, a port for connecting an apparatus having an identification module, an audio input/output (I/O) port, a video I/O port, a headset jack, or the like. The interface unit **408** may be configured to receive input (for example, data information and power) from an external apparatus and transmit the received input to one or more elements in the terminal device **400** or may be configured to transmit data between the terminal device **400** and the external apparatus.

(149) The terminal device **400** may further include the power supply **411** (such as a battery) that supplies power to each component. In some embodiments, the power supply **411** may be logically connected to the processor **410** by using a power management system, to implement functions such as charging, discharging, and power consumption management by using the power management system.

(150) In addition, the terminal device **400** includes some functional modules not shown, and details are not described herein.

(151) An embodiment of the present disclosure further provides a network side device, including a processor, a memory, and a computer program that is stored in the memory and that can be run on the processor. When the computer program is executed by the processor, processes of the foregoing embodiments of the method for determining a measurement target, applied to a network device, are implemented, and a same technical effect can be achieved. To avoid repetition, details are not described herein.

(152) FIG. 5 is a schematic diagram of a hardware structure of a network side device according to an embodiment of the present disclosure. The network side device includes: a memory **501**, a processor **502**, a transceiver **503**, and a computer program that is stored in the memory **501** and that can be run by the processor **502**.

(153) The transceiver **503** may be configured to send configuration information to a terminal device, where the configuration information includes that a parameter reportQuantity is set to null, and the configuration information is used by the terminal device to determine the measurement target, where the measurement target includes SINR measurement or RSRP measurement.

(154) In FIG. 5, a bus architecture may include any quantity of interconnected buses and bridges, and specifically links various circuits of one or more processors represented by the processor **502** and a memory represented by the memory **501**. The bus architecture may further link various other circuits such as those of a peripheral device, a voltage regulator, and a power management circuit. These are well known in the art, and therefore are not further described in this specification. The bus interface provides an interface. The transceiver **503** may be a plurality of elements, namely, include a transmitter and a transceiver, and provide a unit configured to communicate with various other apparatuses on a transmission medium, and is configured to receive and send data under the control of the processor **502**. The processor **502** is responsible for managing the bus architecture and common processing, and the memory **501** may store data used when the processor **502** performs an operation.

(155) According to this embodiment, the processor **502** can run a computer program stored in the memory **501**, and processes of the foregoing embodiments of the method for determining a measurement target, applied to a network device, are implemented, and a same technical effect can be achieved. To avoid repetition, details are not described herein.

(156) An embodiment of the present disclosure further provides a computer-readable storage medium. The computer-readable storage medium stores a computer program instruction. When the computer program instruction is executed by a processor, processes of the embodiments of the method for determining a measurement target, applied to a terminal device, according to the embodiments of the present disclosure, or processes of the embodiments of the method for determining a measurement target, applied to a network side device, according to the embodiments of the present disclosure are implemented, and a same technical effect can be achieved. To avoid repetition, details are not described herein again. An example of the computer-readable storage medium includes a non-transitory computer-readable storage medium, such as a Read-Only Memory (ROM), a Random Access Memory (RAM), a magnetic disk, an optical disc, or the like.

(157) The foregoing describes the aspects of the present disclosure with reference to flowcharts and/or block diagrams of the method, the apparatus (system), and the computer program product according to the embodiments of the present disclosure. It should be understood that each block in the flowchart and/or block diagram and a combination of blocks in the flowchart and/or block diagram may be implemented by a computer program instruction. These computer program instructions may be provided for a general-purpose computer, a dedicated computer, or a processor of another programmable data processing apparatus to generate a machine, so that when these instructions are executed by the computer or the processor of the another programmable data processing apparatus, specific functions/actions in one or more blocks in the flowcharts and/or in

the block diagrams are implemented. The processor may be but is not limited to a general purpose processor, a dedicated processor, a special application processor, or a field programmable logic circuit. It should be further understood that each block in the block diagram or the flowchart and a combination of blocks in the block diagram or the flowchart may be implemented by using dedicated hardware that performs a specified function or operation, or may be implemented by using a combination of dedicated hardware and a computer instruction.

(158) It should be noted that in this specification, the terms “comprise”, “include” and any other variants thereof are intended to cover non-exclusive inclusion, so that a process, a method, an article, or an apparatus that includes a series of elements not only includes those elements, but may also include other elements not expressly listed, or also include elements inherent to this process, method, article, or apparatus. An element limited by “includes a . . . ” does not, without more constraints, preclude the presence of additional identical elements in the process, method, article, or apparatus that includes the element.

(159) The embodiments of the present disclosure are described above with reference to the accompanying drawings, but the present disclosure is not limited to the foregoing specific implementations. The foregoing specific implementations are merely exemplary instead of restrictive. Under enlightenment of the present disclosure, a person of ordinary skill in the art may make many forms without departing from the aims of the present disclosure and the protection scope of claims, all of which fall within the protection scope of the present disclosure.

Claims

1. A method for determining a measurement target, comprising: receiving configuration information from a network side device, wherein the configuration information comprises that a parameter reportQuantity of a Channel State Information (CSI) report is set to null, and the configuration information is used for a terminal device to determine the measurement target, wherein the measurement target comprises a Signal to Interference plus Noise Ratio (SINR) measurement or a Reference Signal Received Power (RSRP) measurement; and determining the measurement target according to the configuration information, wherein the configuration information comprises any one of the following: at least one Reference Signal (RS) resource setting used for channel measurement and at least one RS resource setting used for interference measurement; or at least one Channel Measurement Resource (CMR) setting and at least one Interference Measurement Resource (IMR) setting; and determining the measurement target according to the configuration information comprises: determining that the measurement target is the SINR measurement.
2. The method according to claim 1, wherein a configuration parameter of a Channel State Information-Reference Signal (CSI-RS) resource set used for the channel measurement in the configuration information does not comprise a tracking reference signal information trs-info parameter, or a configuration parameter of the CSI-RS resource set used for the interference measurement in the configuration information does not comprise the trs-info parameter.
3. The method according to claim 1, further comprising: determining, according to the configuration information, that a quantity ratio of the CMR to the IMR is a preset ratio.
4. The method according to claim 1, further comprising: determining the time occupied by a CSI processing unit required for the CSI report, wherein the CSI report comprises a SINR measurement result.
5. The method according to claim 4, wherein the CSI report is a semi-persistent CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a first symbol to a second symbol, wherein: the first symbol is a 1.sup.st symbol in the earliest transmission occasion of a first RS resource and a second RS resource used for SINR calculation; the second symbol is a Z.sub.i'.sup.th symbol after the last symbol of the latest RS resource in a transmission occasion of

the first RS resource and the second RS resource used for the SINR calculation; the first RS resource is a periodic or semi-persistent Channel State Information-Reference Signal (CSI-RS) resource or a Synchronization Signal Block (SSB) resource used for the channel measurement; and the second RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

6. The method according to claim 4, wherein the CSI report is an aperiodic CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a third symbol to a fourth symbol, wherein: the third symbol is a 1st symbol after a Physical Downlink Control Channel (PDCCH) configured to trigger the CSI report; the fourth symbol is the last symbol between a Z_{sub.j}^{sup.th} symbol and a Z_{sub.j'}^{sup.th} symbol; the Z_{sub.j}^{sup.th} symbol is a Z_{sub.j}^{sup.th} symbol after the first symbol after the PDCCH configured to trigger the CSI report; the Z_{sub.j'}^{sup.th} symbol is a Z_{sub.j'}^{sup.th} symbol after the last symbol of the latest RS resource between a third RS resource and a fourth RS resource used for SINR calculation; the third RS resource is a periodic or semi-persistent CSI-RS resource or Synchronization Signal Block (SSB) resource used for the channel measurement; and the fourth RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

7. The method according to claim 1, further comprising: determining that the measurement target is the RSRP measurement when the configuration information comprises one CMR setting.

8. The method according to claim 7, wherein a configuration parameter of a Channel State Information-Reference Signal (CSI-RS) resource set in the configuration information does not comprise a trs-info parameter.

9. A terminal device, comprising: a memory storing a computer program and a processor, wherein the computer program, when executed by the processor, cause the processor to execute operations for determining a measurement target, the operations comprising: receiving configuration information from a network side device, wherein the configuration information comprises that a parameter reportQuantity of a Channel State Information (CSI) report is set to null, and the configuration information is used for a terminal device to determine the measurement target, wherein the measurement target comprises a Signal to Interference plus Noise Ratio (SINR) measurement or a Reference Signal Received Power (RSRP) measurement; and determining the measurement target according to the configuration information, wherein the configuration information comprises any one of the following: at least one Reference Signal (RS) resource setting used for channel measurement and at least one RS resource setting used for interference measurement; or at least one Channel Measurement Resource (CMR) setting and at least one Interference Measurement Resource (IMR) setting; and determining the measurement target according to the configuration information comprises: determining that the measurement target is the SINR measurement.

10. The terminal device according to claim 9, wherein the operations further comprise: determining, according to the configuration information, that a quantity ratio of the CMR to the IMR is a preset ratio.

11. The terminal device according to claim 9, wherein a configuration parameter of a Channel State Information-Reference Signal (CSI-RS) resource set used for the channel measurement in the configuration information does not comprise a tracking reference signal information trs-info parameter, or a configuration parameter of the CSI-RS resource set used for the interference measurement in the configuration information does not comprise the trs-info parameter.

12. A network side device, comprising: a memory storing a computer program and a processor, wherein the computer program, when executed by the processor, cause the processor to execute operations for determining a measurement target, the operations comprising: sending configuration information to a terminal device, wherein the configuration information comprises a parameter reportQuantity of a Channel State Information (CSI) report that is set to null, and the configuration information is used by the network side device to determine the measurement target, wherein the

measurement target comprises a Signal to Interference plus Noise Ratio (SINR) measurement or a Reference Signal Received Power (RSRP) measurement, wherein the configuration information comprises any one of the following: at least one Reference Signal (RS) resource setting used for channel measurement and at least one RS resource setting used for interference measurement; or at least one Channel Measurement Resource (CMR) setting and at least one Interference Measurement Resource (IMR) setting; and determining the measurement target according to the configuration information comprises; determining that the measurement target is the SINR measurement.

13. The network side device according to claim 12, wherein a configuration parameter of a CSI-RS resource set used for the channel measurement in the configuration information does not comprise a trs-info parameter, or a configuration parameter of the CSI-RS resource set used for the interference measurement in the configuration information does not comprise the trs-info parameter.

14. The network side device according to claim 12, wherein the configuration information is further used to indicate that a quantity ratio of the CMR to the IMR comprised in the RS resource is a preset ratio.

15. The network side device according to claim 12, wherein the operations further comprise: determining the time occupied by a CSI processing unit required for the CSI report, wherein the CSI report comprises a SINR measurement result.

16. The network side device according to claim 15, wherein the CSI report is a semi-persistent CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a first symbol to a second symbol, wherein: the first symbol is a 1.sup.st symbol in the earliest transmission occasion of a first RS resource and a second RS resource used for SINR calculation; the second symbol is a Z.sub.i'.sup.th symbol behind the last symbol of the latest RS resource in a transmission occasion of the first RS resource and the second RS resource used for the SINR calculation; the first RS resource is a periodic or semi-persistent Channel State Information-Reference Signal (CSI-RS) resource or a Synchronization Signal Block (SSB) resource used for the channel measurement; and the second RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

17. The network side device according to claim 15, wherein the CSI report is an aperiodic CSI report; and the time occupied by the CSI processing unit required for the CSI report is from a third symbol to a fourth symbol, wherein: the third symbol is a 1.sup.st symbol after a Physical Downlink Control Channel (PDCCH) configured to trigger the CSI report; the fourth symbol is the last symbol between a Z.sub.j.sup.th symbol and a Z.sub.j'.sup.th symbol; the Z.sub.j.sup.th symbol is a Z.sub.j.sup.th symbol after the first symbol after the PDCCH configured to trigger the CSI report; the Z.sub.j'.sup.th symbol is a Z.sub.j'.sup.th symbol after the last symbol of the latest RS resource between a third RS resource and a fourth RS resource used for SINR calculation; the third RS resource is a periodic or semi-persistent CSI-RS resource or Synchronization Signal Block (SSB) resource used for the channel measurement; and the fourth RS resource is a periodic or semi-persistent CSI-RS resource or SSB resource used for the interference measurement.

18. The network side device according to claim 12, wherein the operations further comprise: determining that the measurement target is the RSRP measurement when the configuration information comprises one CMR setting.

19. The network side device according to claim 18, wherein a configuration parameter of a Channel State Information-Reference Signal (CSI-RS) resource set in the configuration information does not comprise a trs-info parameter.
