

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12417875
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Tsuchida; Masahiro et al.

Electronic device

Abstract

An electronic device has a substrate, a signal wiring and a heat radiating wiring. The substrate has one surface and the other surface opposite to the one surface. The signal wiring is formed on an insulating layer of the substrate. The heat radiating wiring is formed on the insulating layer and thermally connected to the signal wiring on a same plane as the signal wiring.

Inventors: Tsuchida; Masahiro (Nisshin, JP), Yamaguchi; Akihiro (Nisshin, JP), Kojima; Ryota (Nisshin, JP)

Applicant: DENSO CORPORATION (Kariya, JP); TOYOTA JIDOSHA KABUSHIKI KAISHA (Toyota, JP); MIRISE Technologies Corporation (Nisshin, JP)

Family ID: 1000008819426

Assignee: DENSO CORPORATION (Kariya, JP); TOYOTA JIDOSHA KABUSHIKI KAISHA (Toyota, JP); MIRISE Technologies Corporation (Nisshin, JP)

Appl. No.: 17/555594

Filed: December 20, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20220301762 A1	Sep. 22, 2022

Foreign Application Priority Data

JP	2021-042664	Mar. 16, 2021
JP	2021-120694	Jul. 21, 2021

Publication Classification

Int. Cl.: H01F27/28 (20060101); H01F27/24 (20060101); H05K1/11 (20060101)

U.S. Cl.:

CPC H01F27/2876 (20130101); H01F27/24 (20130101); H01F27/2804 (20130101);
H05K1/115 (20130101); H01F2027/2809 (20130101)

Field of Classification Search

CPC: H01F (27/2876); H01F (27/24); H01F (27/2804); H01F (2027/2809)

USPC: 336/61

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2010/0164670	12/2009	Nakahori	336/200	H01F 27/306
2012/0195005	12/2011	Asano et al.	N/A	N/A
2015/0183456	12/2014	Nishimura	N/A	N/A
2016/0035480	12/2015	Hachiya et al.	N/A	N/A
2016/0035481	12/2015	Hachiya et al.	N/A	N/A
2019/0180923	12/2018	Nakajima et al.	N/A	N/A
2019/0320554	12/2018	Nakajima et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2007059839	12/2006	JP	N/A
2008177486	12/2007	JP	N/A
2010153724	12/2009	JP	H01F 27/2804
2011077328	12/2010	JP	N/A
2013062355	12/2012	JP	N/A
2014036033	12/2013	JP	N/A
2015018857	12/2014	JP	N/A
2015-079778	12/2014	JP	N/A
2018-186596	12/2017	JP	N/A
2019-165148	12/2018	JP	N/A
20190072729	12/2018	KR	N/A
WO-2011010491	12/2010	WO	H01F 27/22
WO-2014141672	12/2013	WO	H01F 27/22

Primary Examiner: Ismail; Shawki S

Assistant Examiner: Baisa; Joselito S.

Attorney, Agent or Firm: Posz Law Group, PLC

Background/Summary

CROSS REFERENCE TO RELATED APPLICATION

(1) This application is based on Japanese Patent Application No. 2021-042664 filed on Mar. 16, 2021 and Japanese Patent Application No. 2021-120694 filed on Jul. 21, 2021, the disclosures of which are incorporated herein by reference in their entirety.

TECHNICAL FIELD

(2) The present disclosure relates to an electronic device having a signal wiring.

BACKGROUND ART

(3) An electronic device such as power conversion device has a primary winding and a secondary winding as signal wiring. An insulating plate is arranged between the primary winding and the secondary winding.

SUMMARY

(4) According to an aspect of the present disclosure, an electronic device has a substrate with one surface and the other surface opposite to the one surface. A signal wiring is formed on an insulating layer of the substrate. A heat radiating wiring formed on the insulating layer is thermally connected to the signal wiring on the same plane as the signal wiring.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) FIG. 1 is a perspective view of a power conversion device according to a first embodiment.
- (2) FIG. 2 is a circuit diagram of a transformer.
- (3) FIG. 3 is an exploded perspective view of a transformer configuration region.
- (4) FIG. 4A is a plan view of a first constituent layer.
- (5) FIG. 4B is a plan view of a second constituent layer.
- (6) FIG. 4C is a plan view of a third constituent layer.
- (7) FIG. 5A is a cross-sectional view taken along a line VA-VA in FIG. 1.
- (8) FIG. 5B is a cross-sectional view taken along a line VB-VB in FIG. 1.
- (9) FIG. 6 is a diagram for explaining an issue that may occur when a heat radiating wiring is not divided.
- (10) FIG. 7 is an exploded perspective view of a transformer configuration region in a modification of the first embodiment.
- (11) FIG. 8A is a plan view of a second constituent layer in a second embodiment.
- (12) FIG. 8B is a plan view of a third constituent layer in the second embodiment.
- (13) FIG. 9A is a plan view of a second constituent layer in a third embodiment.
- (14) FIG. 9B is a plan view of a third constituent layer in the third embodiment.
- (15) FIG. 10 is a perspective view of a power conversion device according to a fourth embodiment.
- (16) FIG. 11 is an exploded perspective view of a pressing member, a one-side heat radiating member, a transformer configuration region, and the other-side heat radiating member.
- (17) FIG. 12 is a cross-sectional view taken along a line XII-XII in FIG. 10.
- (18) FIG. 13 is a perspective view of a power conversion device according to a fifth embodiment.
- (19) FIG. 14 is a perspective view of a power conversion device according to a modification of the fifth embodiment.
- (20) FIG. 15 is a diagram for explaining an issue that may occur when a printed circuit board is fixed on a housing.
- (21) FIG. 16 is a schematic cross-sectional view of a power conversion device according to a sixth embodiment.
- (22) FIG. 17 is a schematic cross-sectional view of a power conversion device according to a modification of the sixth embodiment.
- (23) FIG. 18 is a plan view of a first constituent layer in a seventh embodiment.

(24) FIG. **19** is an exploded perspective view of a transformer configuration region according to an eighth embodiment.

(25) FIG. **20** is a circuit diagram of a transformer according to another embodiment.

DESCRIPTION OF EMBODIMENTS

(26) To begin with, examples of relevant techniques will be described.

(27) Conventionally, an electronic device having a signal wiring is proposed. For example, as an electronic device, a power conversion device has a primary winding and a secondary winding as signal wiring. An insulating plate is arranged between the primary winding and the secondary winding. Further, in the power conversion device, a heat radiating plate is arranged on the primary winding. The power conversion device is configured by stacking the secondary winding, the insulating plate, the primary winding, and the heat radiating plate integrally formed with a molding resin.

(28) For such an electronic device, it is desired to further improve the heat radiation property.

(29) The present disclosure provides an electronic device capable of improving the heat radiation property.

(30) According to an aspect of the present disclosure, an electronic device has a substrate with one surface and the other surface opposite to the one surface. A signal wiring is formed on an insulating layer of the substrate. A heat radiating wiring formed on the insulating layer is thermally connected to the signal wiring on the same plane as the signal wiring.

(31) Accordingly, since the heat radiating wiring is arranged on the same plane as the signal wiring, it is easy to arrange the signal wiring and the heat radiating wiring in close proximity to each other. Therefore, heat can be easily dissipated from the signal wiring through the heat radiating wiring. Thus, the heat radiation property can be improved.

(32) A reference numeral attached to each component or the like indicates an example of correspondence between the component or the like and specific component or the like described in embodiments below.

(33) Hereinbelow, embodiments of the present disclosure will be described with reference to the drawings. In the embodiments, same or equivalent parts are designated with the same reference numerals.

First Embodiment

(34) A first embodiment will be described with reference to the drawings. In the present embodiment, a power conversion device having a transformer T will be described as an electronic device.

(35) As shown in FIG. **1**, the power conversion device of the present embodiment includes a printed circuit board **1** and a housing **2**. The printed circuit board **1** of the present embodiment is a multilayer board in which a signal wiring **100** made of copper or the like and an insulating layer **101** made of an epoxy resin or the like are alternately stacked. The printed circuit board **1** has one surface **1a** and the other surface **1b**.

(36) The printed circuit board **1** has a transformer configuration region **10** which is a predetermined portion for a coil of the transformer T. The transformer configuration region **10** is provided with a core **20** to form a transformer. Although omitted in FIG. **1**, electronic components such as capacitors are appropriately mounted on the printed circuit board **1** in a region different from the transformer configuration region **10**.

(37) As shown in FIG. **2**, the transformer T of the present embodiment has first to third coils **31** to **33**. The first coil **31** has one end connected to the first connection wire **41** and the other end connected to the second connection wire **42**. The first coil **31** is connected to an AC circuit (not shown) via the first connection wire **41** and the second connection wire **42**. The second coil **32** and the third coil **33** are connected in series. The third connection wire **43** is connected to an end of the second coil **32** opposite to the third coil **33**. The fourth connection wire **44** is connected to an end of the third coil **33** opposite to the second coil **32**. The second coil **32** and the third coil **33** are

connected to a rectifier circuit or the like (not shown) via the third connection wire **43** and the fourth connection wire **44**. Further, in the present embodiment, the fifth connection wire **45** is connected between the second coil **32** and the third coil **33**. The fifth connection wire **45** is connected to the housing **2** and maintained at the ground potential, as will be described later.

(38) A signal wiring **100** is formed in the transformer configuration region **10** of the printed circuit board **1** so as to form the first to third coils **31** to **33** and the first to fifth connection wires **41** to **45**. Hereinafter, the transformer configuration region **10** of the present embodiment will be specifically described.

(39) As shown in FIGS. **3**, **4A** to **4C**, **5A**, and **5B**, the transformer configuration region **10** of the present embodiment is configured by stacking the first to fourth constituent layers **110**, **120**, **130**, and **140**. A part of the printed circuit board **1** forms the transformer configuration region **10**. Although an exploded perspective view is shown in FIG. **3**, the transformer configuration region **10** is formed by integrally with the first to fourth constituent layers **110**, **120**, **130**, and **140**. The printed circuit board **1** is configured by stacking the first to fourth constituent layers **140**, similarly to the transformer configuration region **10**. In the following, when the description simply refers to the first to fourth constituent layer **110**, **120**, **130**, **140**, it means the first to fourth constituent layer **110**, **120**, **130**, **140** in the transformer configuration region **10**.

(40) The first to third constituent layer **110**, **120**, **130** includes the signal wiring **100** and the insulating layer **101**. The fourth constituent layer **140** includes the signal wiring **100**. The signal wirings **100** in the first to fourth constituent layer **110**, **120**, **130**, **140** are appropriately electrically connected via the connection via **102** formed in the first to third constituent layer **110**, **120**, **130**. The fourth constituent layer **140** has the signal wiring **100** formed on the side opposite to the second constituent layer **120**, in the insulating layer **101** of the third constituent layer **130**. Therefore, it can be said that the insulating layer **101** in the third constituent layer **130** is shared by the third constituent layer **130** and the fourth constituent layer **140**.

(41) The first to third constituent layers **110**, **120**, and **130** have one central through hole **101a** and two outer periphery through holes **101b** penetrating the insulating layer **101** in the thickness direction. Specifically, the central through hole **101a** is formed in the first to third constituent layers **110**, **120**, and **130** at a substantially central portion, and is interposed between the two outer periphery through holes **101b** in the first to third constituent layers **110**, **120**, and **130**. More specifically, the central through hole **101a** and the outer periphery through hole **101b** are formed at positions and sizes, such that the leg **21b**, **21c**, **22b**, **22c** of the first core **21** or the second core **22**, which will be described later, can be inserted.

(42) The first constituent layer **110** has an upper primary winding **111** arranged around the central through hole **101a** on the insulating layer **101**, as the signal wiring **100** forming a part of the first coil **31** in the transformer T. The upper primary winding **111** of the present embodiment has four turns, and the width is set to allow the four turns. The upper primary winding **111** is arranged between the central through hole **101a** and the outer periphery through hole **101b**.

(43) The first constituent layer **110** has, as the signal wiring **100**, a first lead-out wiring **112** forming the first connection wire **41**. The lead-out wiring **112** is led out from the upper primary winding **111** at one end opposite to the central through hole **101a**. The first constituent layer **110** has, as the signal wiring **100**, a third connection wiring **113** and a fourth connection wiring **114** on a side opposite to the first lead-out wiring **112** through the central through hole **101a**. The third connection wiring **113** is connected to the third lead-out wiring **122** formed in the second constituent layer **120**, which will be described later, via the connection via **102**. The fourth connection wiring **114** is connected to a fourth connection wiring **124** formed on the second constituent layer **120**, which will be described later, via the connection via **102**.

(44) The second constituent layer **120** has a secondary winding **121** as the signal wiring **100** constituting the second coil **32** in the transformer T. The secondary winding **121** is arranged around the central through hole **101a** on the insulating layer **101**. The secondary winding **121** of the

present embodiment has one turn, and the width corresponds to the one turn. The secondary winding **121** is arranged between the central through hole **101a** and the outer periphery through hole **101b**.

(45) The second constituent layer **120** has, as the signal wiring **100**, the third lead-out wiring **122** to form the third connection wire **43**. The third lead-out wiring **122** is led out from one end of the secondary winding **121**. The second constituent layer **120** has a fifth lead-out wiring **123** led out from the other end of the secondary winding **121** to form the fifth connection wire **45** as the signal wiring **100**. The fifth lead-out wiring **123** has a fastening hole **123a** through which a fastening member **60**, which will be described later, is inserted. The fastening hole **123a** is formed so as to penetrate the fifth lead-out wiring **123** and the insulating layer **101**. Further, in the present embodiment, the third lead-out wiring **122** corresponds to a first end lead-out wiring, and the fifth lead-out wiring **123** corresponds to a second end lead-out wiring. The second constituent layer **120** has the fourth connection wiring **124** connected to a fourth lead-out wiring **132** formed in the third constituent layer **130**, which will be described later, via the connection via **102**.

(46) The third lead-out wiring **122** and the fifth lead-out wiring **123** of the present embodiment are formed on the same side as the third connection wiring **113** and the fourth connection wiring **114** in the first constituent layer **110**. In other words, the third lead-out wiring **122** and the fifth lead-out wiring **123** are located at a position opposite to a portion of the second constituent layer **120** facing the first lead-out wiring **112** in the first constituent layer **110** through the central through hole **101a**.

(47) The third constituent layer **130** has a tertiary winding **131** arranged around the central through hole **101a** on the insulating layer **101**, as the signal wiring **100** constituting the third coil **33** in the transformer T. The tertiary winding **131** of the present embodiment has one turn, and the width corresponds to the one turn. The tertiary winding **131** is arranged between the central through hole **101a** and the outer periphery through hole **101b**.

(48) The third constituent layer **130** has, as the signal wiring **100**, a fourth lead-out wiring **132** led out from one end of the tertiary winding **131** to form the fourth connection wire **44**. The third constituent layer **130** has a fifth lead-out wiring **133** led out from the other end of the tertiary winding **131** to form the fifth connection wire **45** as the signal wiring **100**. The fifth lead-out wiring **133** has a fastening hole **133a** through which a fastening member **60**, which will be described later, is inserted. The fastening hole **133a** is formed so as to penetrate the fifth lead-out wiring **133** and the insulating layer **101**. Further, in the present embodiment, the fourth lead-out wiring **132** corresponds to a first end lead-out wiring, and the fifth lead-out wiring **133** corresponds to a second end lead-out wiring. The third constituent layer **130** has a third connection wiring **134** connected to a third connection wiring **143** of the fourth constituent layer **140**, which will be described later, via the connection via **102**.

(49) The fourth lead-out wiring **132** and the fifth lead-out wiring **133** of the present embodiment are formed on the same side as the third connection wiring **113** and the fourth connection wiring **114** in the first constituent layer **110**. In other words, the fourth lead-out wiring **132** and the fifth lead-out wiring **133** are located opposite to a portion of the third constituent layer **120** facing the first lead-out wiring **112** in the first constituent layer **110** through the central through hole **101a**.

(50) The fourth constituent layer **140** is arranged on the side opposite to the surface of the insulating layer **101** of the third constituent layer **130** on which the tertiary winding **131** is formed. The fourth constituent layer **140** has a lower primary winding **141** as the signal wiring **100** arranged around the central through hole **101a** formed in the insulating layer **101** of the third constituent layer **130**. The lower primary winding **141** of the present embodiment has four turns, and the width is set to allow the four turns. The lower primary winding **141** is arranged between the central through hole **101a** and the outer periphery through hole **101b** formed in the third constituent layer **130**. The other end of the lower primary winding **141** adjacent to the central through hole **101a** is electrically connected to the other end of the upper primary winding **111** adjacent to the central through hole **101a** via the connection via **102** formed in the first to third constituent layers

110, 120, 130. Therefore, the first coil **31** of the present embodiment is composed of the upper primary winding **111** and the lower primary winding **141**.

(51) The fourth constituent layer **140** has, as the signal wiring **100**, a second lead-out wiring **142** led out from one end of the lower primary winding **141** opposite to the central through hole **101a** to form the second connection wire **42**. The fourth constituent layer **140** has, as the signal wiring **100**, the third connection wiring **143** connected to the third connection wiring **134** of the third constituent layer **130** via the connection via **102**, and the fourth connection wiring **144** connected to the fourth lead-out wiring **132** via the connection via **102**.

(52) The second lead-out wiring **142** is formed on the same side as the first lead-out wiring **112** in the first constituent layer **110**. Further, the third connection wiring **143** and the fourth connection wiring **144** are formed on the side opposite to the second lead-out wiring **142** through the central through hole **101a**.

(53) In the present embodiment, as described above, the first coil **31** is configured by the primary windings **111** and **141** formed in the first and fourth constituent layers **110** and **140**. The second coil **32** is configured by the secondary winding **121** formed on the second constituent layer **120**. The third coil **33** is formed by the tertiary winding **131** formed in the third constituent layer **130**.

Further, the first connection wire **41** is formed by the first lead-out wiring **112** formed in the first constituent layer **110**. The second connection wire **42** is formed by the second lead-out wiring **142** formed in the fourth constituent layer **140**. The third connection wire **43** is formed by the third lead-out wiring **122** formed in the second constituent layer **120**. The fifth connection wire **45** is formed by the fifth lead-out wiring **123**. The fourth connection wire **44** is formed by the fourth lead-out wiring **132** in the third constituent layer **130**. The fifth connection wire **45** is formed by the fifth lead-out wiring **133**.

(54) Further, the first to fourth constituent layers **140** have a heat radiating wiring **150**. Specifically, the first constituent layer **110** has the heat radiating wiring **150** arranged around the upper primary winding **111** on the insulating layer **101** so as to be thermally connected to the upper primary winding **111**. The second constituent layer **120** has the heat radiating wiring **150** thermally connected to the secondary winding **121** around the secondary winding **121**. The third constituent layer **130** has the heat radiating wiring **150** that is thermally connected to the tertiary winding **131** around the tertiary winding **131**. The fourth constituent layer **140** has the heat radiating wiring **150** that is thermally connected to the lower primary winding **141** around the lower primary winding **141**. That is, each of the first to fourth constituent layers **140** has the heat radiating wiring **150** on the same plane as the winding **111, 121, 131, 141**. The heat radiating wiring **150** is made of, for example, copper or the like, similarly to the signal wiring **100**.

(55) Each heat radiating wiring **150** has a fastening hole **151** for inserting a fastening member **60**, which will be described later. Specifically, each heat radiating wiring **150** is divided as described later, and the fastening hole **151** is formed in each of the divided regions. The fastening hole **151** is formed so as to penetrate the heat radiating wiring **150** and the insulating layer **101**. Further, the fastening holes **151** in the heat radiating wirings **150** of the first to fourth constituent layers **110, 120, 130, and 140** are formed at the same positions in the normal direction with respect to the one surface **1a** of the printed circuit board **1**. The heat radiating wirings **150** formed in the first to fourth constituent layers **110, 120, 130, and 140** are thermally connected to each other via the connection via **102**. That is, each heat radiating wiring **150** formed in the second to fourth constituent layers **120, 130, 140** is thermally connected to the heat radiating wiring **150** formed in the first constituent layer **110**. In other words, each heat radiating wiring **150** formed in the first to third constituent layers **110 to 130** is thermally connected to the heat radiating wiring **150** formed in the fourth constituent layer **140**.

(56) The core **20** of the printed circuit board **1** is made of a magnetic material such as ferrite, and includes a first core **21** and a second core **22**. In the present embodiment, the first core **21** has a base portion **21a**, an inner leg **21b** extending from the base portions **21a**, and a pair of outer legs

21c extending from the base portions **21a**. The second core **22** has a base portion **22a**, an inner leg **22b** extending from the base portions **22a**, and a pair of outer legs **22c** extending from the base portions **22a**.

(57) The base portion **21a**, **22a** has a flat plate shape with one direction as the longitudinal direction. The inner leg **21b**, **22b** projects in the normal direction with respect to the surface direction of the base portion **21a**, **22a** at the central portion in the longitudinal direction of the base portion **21a**, **22a**. The pair of outer legs **21c**, **22c** are formed so as to project in the normal direction with respect to the surface direction of the base portion **21a**, **22a** at both ends of the base portion **21a**, **22a** in the longitudinal direction. That is, each of the first core **21** and the second core **22** of the present embodiment is so-called E-type core.

(58) The first core **21** is arranged so that the inner leg **21b** is inserted into the central through hole **101a** from the one surface **1a** of the printed circuit board **1** and each outer leg **21c** is inserted into each outer periphery through hole **101b**. The second core **22** is arranged so that the inner leg **22b** is inserted into the central through hole **101a** from the other surface **1b** of the printed circuit board **1** and each outer leg **22c** is inserted into each outer periphery through hole **101b**. That is, the first core **21** and the second core **22** are arranged so as to oppose each other. As a result, a closed magnetic path is formed in the transformer configuration region **10**. The protrusion height of the inner legs **21b** and **22b** and the outer legs **21c** and **22c** are adjusted so that the inner legs **21b** and **22b** are in contact with each other and the outer legs **21c** and **22c** are in contact with each other when the first core **21** and the second core **22** are arranged on the printed circuit board **1**.

(59) Further, in the present embodiment, a heat radiating member **50** which is made of an insulating material having high thermal conductivity is arranged between the core **20** and the printed circuit board **1**. The heat radiating member **50** is composed of a heat radiating grease, a heat radiating gap filler, a heat radiating putty sheet, a heat radiating gel sheet, or the like.

(60) The heat radiating wiring **150** of the present embodiment is formed in each winding **111**, **121**, **131**, **141**, and is divided at a portion where each of the lead-out wirings **112**, **122**, **123**, **132**, **133**, **142** is formed. The heat radiating wiring **150** of the present embodiment is further divided into plural regions in the normal direction with respect to the surface direction of the printed circuit board **1**. Specifically, as shown in FIG. 4A, the heat radiating wiring **150** of the first constituent layer **110** is divided into a region located on one side of the core **20** and a region located on the other side of the core **20** with reference to a virtual line K passing through the upper primary winding **111** and extending along one direction in the surface direction of the printed circuit board **1**. In other words, the heat radiating wiring **150** is divided around the upper primary winding **111** so as not to form a winding, and is arranged so as not to exert a function as a coil. In the present embodiment, the heat radiating wiring **150** is divided into a region located on one side of the core **20** and a region located on the other side of the core **20** in a portion overlapping the core **20**.

(61) Similarly, the heat radiating wiring **150** of the second and third constituent layers **120** and **130** is divided in the same manner as the heat radiating wiring **150** of the first constituent layer **110**. That is, as shown in FIG. 4B or FIG. 4C, the heat radiating wiring **150** of the second and third constituent layers **120** and **130** is divided into a region located on one side of the core **20** and a region located on the other side of the core **20** with respect to the virtual line K extending along one direction in the surface direction of the printed circuit board **1**. Further, although the details of the heat radiating wiring **150** of the fourth constituent layer **140** are not shown, as shown in FIG. 3, the heat radiating wiring **150** is divided into a region located on one side of the core **20** and a region located on the other side of the core **20** with reference to the virtual line extending along one direction in the surface direction of the printed circuit board **1**.

(62) The housing **2** is made of a conductive material and has a predetermined shape. The printed circuit board **1** is fixed on the housing via a fastening member **60** such as a screw so that the other surface **1b** faces the housing **2**. The housing **2** of the present embodiment releases heat from the printed circuit board **1** and also functions as a heat radiating body.

(63) The printed circuit board **1** is fixed on the housing **2** via the fastening member **60** at a predetermined position on the outer periphery portion. The printed circuit board **1** is fixed on the housing **2** via the fastening member **60** passing through a fastening hole **123a** formed in the fifth lead-out wiring **123** of the second constituent layer **120** and a fastening hole **133a** formed in the fifth lead-out wiring **133** of the third constituent layer **130** in the transformer configuration region **10**. As a result, the fifth lead-out wiring **123**, **133** is thermally and electrically connected to the housing **2**. Further, the printed circuit board **1** is fixed to the housing **2** in the transformer configuration region **10** via a fastening member **60** inserted in the fastening hole **151** formed in the heat radiating wiring **150**. As a result, the heat radiating wiring **150** formed in the first constituent layer **110** is thermally connected to the housing **2** via the fastening member **60**. Further, since the heat radiating wiring **150** formed in the second to fourth constituent layer **120**, **130**, **140** is thermally connected to the heat radiating wiring **150** formed in the first constituent layer **110**, the printed circuit board **1** is thermally connected to the housing **2** via the heat radiating wiring **150** formed in the first constituent layer **110** and the fastening member **60**. That is, all the heat radiating wirings **150** formed in the first to fourth constituent layers **110**, **120**, **130**, **140** are thermally connected to the housing **2** via the fastening member **60**. Further, as shown in FIG. 5B, the fourth constituent layer **140** is arranged so that the heat radiating wiring **150** of the fourth constituent layer **140** is in direct contact with the housing **2**. The heat radiating wiring **150** formed in the first to third constituent layers **110**, **120**, and **130** is thermally connected to the heat radiating wiring **150** formed in the fourth constituent layer **140**. Therefore, the heat radiating wiring **150** formed in the first to third constituent layers **110**, **120**, **130** is thermally connected to the housing **2** via the heat radiating wiring **150** formed in the fourth constituent layer **140**.

(64) As described above, the heat radiating wiring **150** is divided into plural regions. Further, the heat radiating wiring **150** is also divided according to the shape of the signal wiring **100** in each of the constituent layers **110**, **120**, **130**, **140**. However, the heat radiating wirings **150** in each of the constituent layers **110**, **120**, **130**, **140** are appropriately connected through the connection via **102**. The location of the fastening member **60** and the connection via **102** which connects the heat radiating wirings **150** between the constituent layers **110**, **120**, **130**, **140** are adjusted such that all the heat radiating wirings **150** are thermally connected to the housing **2**.

(65) The housing **2** of the present embodiment has a holder **70** made of metal. One end of the holder **70** is located on the printed circuit board **1**, and the other end is fixed. Then, the core **20** is arranged on the printed circuit board **1** so as to be pressed by the one end of the holder **70**.

(66) According to the present embodiment, the heat radiating wiring **150** is arranged on the printed circuit board **1** on the same plane as the windings **111**, **121**, **131**, **141**. Therefore, the heat radiating wiring **150** can be easily arranged in the vicinity of the windings **111**, **121**, **131**, **141**, such that the heat radiating property can be improved.

(67) (1) In the present embodiment, the transformer **T** is configured by using the printed circuit board **1** as a multilayer board. Therefore, the size can be reduced as compared with a case where members corresponding to the signal wiring **100**, the insulating layer **101**, the heat radiating wiring **150**, and the like in the present embodiment are separately prepared and stacked.

(68) (2) In the present embodiment, the heat radiating member **50** is arranged between the printed circuit board **1** and the core **20**. Therefore, the heat of the printed circuit board **1** can be released from the core **20** via the heat radiating member **50**. In this embodiment, the core **20** is pressed against the holder **70**. Therefore, heat can be dissipated from the printed circuit board **1** to the housing **2** via the core **20** and the holder **70**.

(69) (3) In the present embodiment, the heat radiating wiring **150** is divided into a region located on one side of the core **20** and a region located on the other side of the core **20** with reference to the virtual line **K** extending along one direction in the surface direction of the printed circuit board **1**. That is, the heat radiating wiring **150** is arranged so as not to function as a coil. Therefore, the loss of the transformer **T** can be reduced as compared with a case where the heat radiating wiring **150** is

not divided in this way. That is, when the heat radiating wiring **150** is not divided, the heat radiating wiring **150** may function as a coil by forming the heat radiating wiring **150** around the windings **111**, **121**, **131**, **141**. In this case, as shown in FIG. **6**, the heat radiating wiring **150** functions as a coil, so that a short-circuit current flows through the heat radiating wiring **150**, causing a loss in the transformer T. In contrast, the heat radiating wiring **150** of this embodiment is arranged so as not to function as a coil. Therefore, it is possible to suppress the occurrence of loss in the transformer T due to the short-circuit current flowing through the heat radiating wiring **150**.

Modification of First Embodiment

(70) A modification of the first embodiment will be described. In the first embodiment, the configuration of the transformer configuration region **10** can be changed as appropriate. For example, as shown in FIG. **7**, in the transformer configuration region **10**, the first constituent layer **110** in which the primary winding **111** is formed and the second constituent layer **120** in which the secondary winding **121** is formed are stacked with each other. Note that FIG. **7** shows an example in which each of the primary winding **111** and the secondary winding **121** has one turn. Further, although not particularly shown, the second coil **32** may be configured by connecting windings formed in different constituent layers, similarly to the first coil **31**. Similarly, the third coil **33** may be configured by connecting windings formed in different constituent layers, similarly to the first coil **31**.

Second Embodiment

(71) A second embodiment will be described below. This embodiment is a modification of the first embodiment in which the configurations of the second constituent layer **120** and the third constituent layer **130** are changed. Descriptions of the same configurations and processes as those of the first embodiment will not be repeated hereinafter.

(72) In the power conversion device of the present embodiment, as shown in FIG. **8A**, in the second constituent layer **120**, the fifth lead-out wiring **123** and the heat radiating wiring **150** are connected with each other. Further, as shown in FIG. **8B**, in the third constituent layer **130**, the fifth lead-out wiring **133** and the heat radiating wiring **150** are connected with each other. That is, a part of the heat radiating wiring **150** of the present embodiment functions as the signal wiring **100**.

(73) According to the present embodiment, since the heat radiating wiring **150** is arranged on the same plane as the windings **111**, **121**, **131**, **141**, the same effect as that of the first embodiment can be obtained.

(74) (1) In the present embodiment, the fifth lead-out wiring **123** and the heat radiating wiring **150** are connected in the second constituent layer **120**. In the third constituent layer **130**, the fifth lead-out wiring **133** and the heat radiating wiring **150** are connected. Therefore, as compared with the first embodiment, the area of the fifth lead-out wiring **123**, **133** in the second and third constituent layers **120**, **130** increases. Therefore, the wiring resistance of the fifth lead-out wiring **123**, **133** can be reduced to suppress heat generation in the fifth lead-out wiring **123**, **133**.

Modification of Second Embodiment

(75) A modification of the second embodiment will be described below. In the second embodiment, only one of the fifth lead-out wiring **123** of the second constituent layer **120** and the fifth lead-out wiring **133** of the third constituent layer **130** may be connected to the heat radiating wiring **150**.

Third Embodiment

(76) A third embodiment will be described below. In this embodiment, the configurations of the second constituent layer **120** and the third constituent layer **130** are changed from those of the second embodiment. Descriptions will not be repeated hereinafter since the other configurations and processes are the same as those of the second embodiment.

(77) In the power conversion device of the present embodiment, as shown in FIG. **9A**, in the second constituent layer **120**, the connection region R1 connecting the secondary winding **121** and the fifth lead-out wiring **123** is larger than the connection region R2 connecting the secondary winding **121** and the third lead-out wiring **122**. Further, as shown in FIG. **9B**, in the third

constituent layer **130**, the connection region **R3** connecting the tertiary winding **131** and the fifth lead-out wiring **133** is made larger than the connection region **R4** connecting the tertiary winding **131** and the fourth lead-out wiring **132**.

(78) According to the present embodiment, since the heat radiating wiring **150** is arranged on the same plane as the windings **111**, **121**, **131**, **141**, the same effect as that of the first embodiment can be obtained.

(79) (1) In the present embodiment, the connection region **R1** between the secondary winding **121** and the fifth lead-out wiring **123** is made larger than the connection region **R2** between the secondary winding **121** and the third lead-out wiring **122**. Therefore, as compared with a case where the connection region **R1** between the secondary winding **121** and the fifth lead-out wiring **123** is equal to the connection region **R2** between the secondary winding **121** and the third lead-out wiring **122**, the wiring resistance of the fifth lead-out wiring **123** can be further reduced to suppress heat generation in the fifth lead-out wiring **123**.

(80) Similarly, the connection region **R3** between the tertiary winding **131** and the fifth lead-out wiring **133** is made larger than the connection region **R4** between the tertiary winding **131** and the fourth lead-out wiring **132**. Therefore, as compared with a case where the connection region **R3** between the tertiary winding **131** and the fifth lead-out wiring **133** is equal to the connection region **R4** between the tertiary winding **131** and the fourth lead-out wiring **132**, the wiring resistance of the fifth lead-out wiring **133** can be further reduced to suppress heat generation in the fifth lead-out wiring **133**.

Modification of Third Embodiment

(81) A modification of the third embodiment will be described. In the third embodiment, the size of the connection region may be different only in one of the second constituent layer **120** and the third constituent layer **130**.

Fourth Embodiment

(82) A fourth embodiment will be described. In this embodiment, a one-side heat radiating member and the other-side heat radiating member are arranged, compared with the first embodiment.

Descriptions will not be repeated hereinafter since the other configurations and processes are the same as those of the first embodiment.

(83) In the power conversion device of the present embodiment, as shown in FIGS. **10** to **12**, in the transformer configuration region **10** of the printed circuit board **1**, the one-side heat radiating member **81** is arranged on the one surface **1a** and the other-side heat radiating member **82** is arranged on the other surface **1b**.

(84) The one-side heat radiating member **81** and the other-side heat radiating member **82** have a predetermined thickness and thermal conductivity, and are made of a heat radiating grease, a heat radiating gap filler, a heat radiating putty sheet, a heat radiating gel sheet, or the like made of an insulating material. Note that FIG. **11** shows a sheet-like member as the one-side heat radiating member **81** and the other-side heat radiating member **82**. The one-side heat radiating member **81** and the other-side heat radiating member **82** have insertion holes **81a** and **82a**, respectively, through which the fastening member **60** is inserted. Further, the one-side heat radiating member **81** has a recessed portion **81b** corresponding to the signal wiring **100** in the first constituent layer **110**. The other-side heat radiating member **82** has a recessed portion **82b** corresponding to the signal wiring **100** in the fourth constituent layer **140**. In FIG. **11**, the recessed portion **82b** formed in the other-side heat radiating member **82** is omitted.

(85) A pressing member **90** is arranged on the one surface **1a** of the printed circuit board **1** via the one-side heat radiating member **81**. In the present embodiment, the two pressing members **90** are arranged to press the one-side heat radiating member **81** exposed from the core **20** in the normal direction with respect to the surface direction of the printed circuit board **1**, on both sides through the core **20**. Further, the pressing member **90** has an insertion hole **90a** into which the fastening member **60** is inserted. The pressing member **90** of the present embodiment is made of copper or

the like.

(86) Then, the printed circuit board **1** is arranged in the housing **2** so that the other-side heat radiating member **82** is located between the other surface **1b** and the housing **2** and the other-side heat radiating member **82** side abuts on the housing **2**. Further, the printed circuit board **1** is fixed on the housing **2** via the fastening member **60** in a state where the one-side heat radiating member **81** and the pressing member **90** are arranged on the one surface **1a**, and the fastening member **60** is thermally connected to the pressing member **90**.

(87) According to the present embodiment, since the heat radiating wiring **150** is arranged on the same plane as the windings **111**, **121**, **131**, **141**, the same effect as that of the first embodiment can be obtained.

(88) (1) In the present embodiment, the other-side heat radiating member **82** is arranged between the housing **2** and the printed circuit board **1**. Therefore, heat can be radiated from the windings **111**, **121**, **131**, **141** of the first to third coils **31** to **33** to the housing **2** via the other-side heat radiating member **82**. Thus, the heat radiating property can be further improved.

(89) (2) In the present embodiment, the one-side heat radiating member **81** is arranged on the one surface **1a** of the printed circuit board **1**. Therefore, the heat of the windings **111**, **121**, **131**, **141** of the first to third coils **31** to **33** is also transmitted to the pressing member **90** via the one-side heat radiating member **81**. Since the pressing member **90** is thermally connected to the fastening member **60**, the heat radiating to the housing **2** can be further improved.

Fifth Embodiment

(90) A fifth embodiment will be described. In this embodiment, the pressing member **90** and the holder **70** are integrated with respect to the fourth embodiment. Descriptions of the same configurations and processes as those of the fourth embodiment will not be repeated hereinafter.

(91) In the power conversion device of the present embodiment, as shown in FIG. **13**, the pressing member **90** has two supporting portions **90b** located on the one surface **1a** of the printed circuit board **1** and fastened by the fastening member **60**, and one pressing portion **90c** located on the core **20**. The shape of the pressing portion **90c** is adjusted so that the core **20** can be pressed. The pressing member **90** of the present embodiment is configured such that two supporting portions **90b** are connected with each other by the one pressing portion **90c**. That is, the pressing member **90** of the present embodiment is composed of one member. Further, the power conversion device of the present embodiment does not include the holder **70** described in the first embodiment.

(92) According to the present embodiment, since the heat radiating wiring **150** is arranged on the same plane as the windings **111**, **121**, **131**, **141**, the same effect as that of the first embodiment can be obtained.

(93) (1) According to the present embodiment, since the core **20** is pressed by the pressing member **90**, it is not necessary to provide the holder **70**. Therefore, as compared with the fourth embodiment, the number of parts can be reduced. Further, since the core **20** is pressed by the pressing member **90**, the heat of the core **20** can be dissipated to the housing **2** via the pressing member **90** and the fastening member **60**.

Modification of Fifth Embodiment

(94) A modification of the fifth embodiment will be described below. In the fifth embodiment, as shown in FIG. **14**, the pressing member **90** may have the pressing portion **90c** on each of the two supporting portions **90b**. That is, as compared with the fifth embodiment, in the pressing member **90**, the pressing portion **90c** provided on one supporting portion **90b** and the pressing portion **90c** provided on the other supporting portion **90b** may be separated or may be composed of two members at a predetermined position on the core **20**. According to this, as compared with the fourth embodiment, it becomes easier to adjust the pressing force of the pressing portion **20b** with respect to the core **20**, and the manufacturing process can be simplified.

Sixth Embodiment

(95) A sixth embodiment will be described. In this embodiment, the configuration of a portion of

the printed circuit board **1** on which the fastening member **60** is arranged is adjusted with respect to the first embodiment. Descriptions of the same configurations and processes as those of the first embodiment will not be repeated hereinafter.

(96) In the first embodiment, the outer periphery portion of the printed circuit board **1** is fixed to the housing **2** via the fastening member **60**, and the transformer configuration region **10** is fixed to the housing **2** via the fastening member **60**. That is, the printed circuit board **1** is fixed to the housing **2** at plural places via the fastening member **60**. In this case, as shown in FIG. **15**, if the total thickness of the wiring **200** at the position where the fastening member **60** is arranged is different, the printed circuit board **1** cannot be uniformly fastened to the housing **2**. In this case, the printed circuit board **1** may be tilted with respect to the surface direction of the housing **2**. If the printed circuit board **1** is tilted with respect to the surface direction of the housing **2**, the heat radiating from the printed circuit board **1** to the housing **2** may decrease. In this embodiment, the wiring **200** is a general term for various wirings including the signal wiring **100** and the heat radiating wiring **150**.

(97) Therefore, in the present embodiment, as shown in FIG. **16**, the total thickness of the wiring **200** at the portion where the fastening member **60** is arranged is set to be the same. Thereby, in the present embodiment, the printed circuit board **1** can be uniformly fastened to the housing **2**, and the printed circuit board **1** can be prevented from tilting with respect to the surface direction of the housing **2**. The wiring **200** where the fastening member **60** is arranged may be only the signal wiring **100**, may be only the heat radiating wiring **150**, or may be a combination of the signal wiring **100** and the heat radiating wiring **150**. Further, the wiring **200** may be a dummy wiring for ensuring the thickness, and the use is not particularly limited.

(98) According to the present embodiment, since the heat radiating wiring **150** is arranged on the same plane as the windings **111**, **121**, **131**, **141**, the same effect as that of the first embodiment can be obtained.

(99) (1) In the present embodiment, the total thickness of the wiring **200** at the portion where the fastening member **60** is arranged is the same. Therefore, the printed circuit board **1** can be uniformly fastened to the housing **2**, and the printed circuit board **1** can be prevented from tilting with respect to the surface direction of the housing **2**. Therefore, it is possible to suppress a decrease in heat radiating from the printed circuit board **1** to the housing **2**.

Modification of Sixth Embodiment

(100) A modification of the sixth embodiment will be described. In the sixth embodiment, if the thicknesses of the wiring **200** at the portion where the fastening member **60** is arranged is the same, as shown in FIG. **17**, the wiring **200** may be formed in different layers. That is, if the total thickness of the wiring **200** is the same in the portion where the fastening member **60** is arranged, the layer on which the wiring **200** is formed can be appropriately changed.

Seventh Embodiment

(101) A seventh embodiment will be described. In this embodiment, the configuration of the first constituent layer **110** is changed from that of the first embodiment. Descriptions of the same configurations and processes as those of the first embodiment will not be repeated hereinafter.

(102) In the power conversion device of the present embodiment, as shown in FIG. **18**, a part of the heat radiating wiring **150** in the first constituent layer **110** is led to the outside of the transformer configuration region **10**. In FIG. **18**, the heat radiating wiring **150** on the upper right of the paper surface is led out to the outside of the transformer configuration region **10**. Then, the heat radiating wiring **150** is used as a ground wiring for another electronic component or the like arranged on the printed circuit board **1**. That is, the heat radiating wiring **150** is connected to the signal wiring **100** outside the transformer configuration region **10**.

(103) According to the present embodiment, since the heat radiating wiring **150** is arranged on the same plane as the windings **111**, **121**, **131**, **141**, the same effect as that of the first embodiment can be obtained.

(104) (1) In the present embodiment, the heat radiating wiring **150** connected to the housing **2** is connected to the signal wiring **100** outside the transformer configuration region **10**. That is, the heat radiating wiring **150** connected to the housing **2** is used to maintain the signal wiring **100** outside the transformer configuration region **10** at the ground potential. Therefore, the heat radiating wiring **150** can be used more effectively.

Modification of Seventh Embodiment

(105) A modification of the seventh embodiment will be described. In the seventh embodiment, the heat radiating wiring **150** in the second to fourth constituent layers **120**, **130**, **140** may be connected to the signal wiring **100** outside the transformer configuration region **10**.

Eighth Embodiment

(106) An eighth embodiment will be described hereafter. In this embodiment, the configuration of the transformer configuration region **10** is changed from that of the first embodiment. Descriptions of the same configurations and processes as those of the first embodiment will not be repeated hereinafter.

(107) In the power conversion device of the present embodiment, as shown in FIG. **19**, the transformer configuration region **10** has a constituent layer **160** in which a signal wiring **100** formed on the insulating layer **101** function as a wiring for a coil. Specifically, the constituent layer **160** of the present embodiment has a rectangular shape with one direction as the longitudinal direction. The signal wiring **100** passes through the substantially center of the constituent layer **160** and is formed in a straight line along the longitudinal direction.

(108) Further, two through holes **101c** are formed in the insulating layer **101**, and the signal wiring **100** is interposed between the two through holes **101c**. The through hole **101c** is formed at a position and size into which the leg **21c**, **22c** of the first core **21** or the second core **22** can be inserted.

(109) In the present embodiment, the first core **21** has the base portion **21a** and a pair of outer legs **21c** extending from the base portion **21a**, and the second core **22** has the base portion **22a** and a pair of outer legs **22c** extending from the base portion **22a**. The base portion **21a**, **22a** has a flat plate shape with one direction as the longitudinal direction. The pair of outer legs **21c**, **22c** are formed so as to project in the normal direction with respect to the surface direction of the base portion **21a**, **22a** at both ends in the lateral direction orthogonal to the longitudinal direction of the base portion **21a**, **22a**. That is, each of the first core **21** and the second core **22** of the present embodiment is so-called U-shaped core.

(110) The first and second cores **21** and **22** are arranged to face each other so that the outer leg **21c**, **22c** is inserted into the through hole **101c**. That is, the power conversion device of the present embodiment is configured to have a choke coil.

(111) Further, on the insulating layer **101**, a heat radiating wiring **150** that is thermally connected to the signal wiring **100** is formed around the signal wiring **100**. The heat radiating wiring **150** has a fastening hole **151** in a portion exposed from the core **20**. Although not particularly shown, the heat radiating wiring **150** is fixed to the housing **2** via the fastening member **60**.

(112) According to the present embodiment, since the heat radiating wiring **150** is arranged on the same plane as the signal wiring **100**, the same effect as that of the first embodiment can be obtained.

OTHER EMBODIMENTS

(113) Although the present disclosure has been described in accordance with the embodiments, it is understood that the present disclosure is not limited to such embodiments or structures. The present disclosure encompasses various modifications and variations within the scope of equivalents. In addition, as the various combinations and configurations, which are preferred, other combinations and configurations, including more, less or only a single element, are also within the spirit and scope of the present disclosure.

(114) For example, in each of the embodiments, the number of constituent layers constituting the

printed circuit board **1** can be appropriately changed. In this case, the transformer configuration region **10** may include a constituent layer in which no winding is formed.

(115) Further, in each of the embodiments, the heat radiating member **50** may not be arranged between the core **20** and the printed circuit board **1**.

(116) Then, in the first to seventh embodiments, as shown in FIG. **20**, the second coil **32** and the third coil **33** may not be connected in series, as the transformer T. That is, the sixth connection wire **46** may be connected to an end of the second coil **32** opposite to the third connection wire **43**, and the seventh connection wire **47** may be connected to an end of the third coil **33** opposite to the fourth connection wire **44**. In this case, the fifth lead-out wiring **123** in the second constituent layer **120** constitutes the sixth connection wire **46**, and the fifth lead-out wiring **133** in the third constituent layer **130** constitutes the seventh connection wire **47**. Although not particularly shown, the place where the fastening member **60** is arranged is changed so that the fifth lead-out wiring **123** of the second constituent layer **120** and the fifth lead-out wiring **133** of the second constituent layer **130** are not electrically connected. Thus, the transformer T of FIG. **20** is configured.

(117) Further, in the first to seventh embodiments, the heat radiating wiring **150** may be divided not at a portion overlapping with the core **20** but at a portion exposed from the core **20** in the normal direction. Further, the heat radiating wiring **150** may be further divided by plural virtual lines K. That is, if the heat radiating wiring **150** does not function as a coil, the division position and the division method can be appropriately changed.

(118) Further, in each of the embodiments, the electronic device may not include the core **20**. Even in such an electronic device, heat radiating can be improved by arranging the heat radiating wiring **150** that is thermally connected to the signal wiring **100** on the same plane as the signal wiring **100**.

(119) In the fourth embodiment, the electronic device may include only one of the one-side heat radiating member **81** and the other-side heat radiating member **82**. When only the other-side heat radiating member **82** is provided, the pressing member **90** may not be arranged.

(120) The above embodiments may be combined as appropriate. For example, the fourth embodiment may be combined with each embodiment to include the one-side heat radiating member **81** and the other-side heat radiating member **82**. In this case, the pressing member **90** may be provided with the pressing portion **90c** as in the fifth embodiment. Further, the sixth embodiment may be combined with each embodiment so that the total thickness of the wiring **200** at the portion where the fastening member **60** is arranged is the same as each other. The seventh embodiment may be combined with each embodiment, and the heat radiating wiring **150** may be connected to the signal wiring **100** outside the transformer configuration region **10**.

Claims

1. An electronic device comprising: a substrate having one surface and the other surface opposite to the one surface; a signal wiring formed on an insulating layer of the substrate; and a heat radiating wiring formed on the insulating layer and thermally connected to the signal wiring on a same plane as the signal wiring, wherein the substrate has a through hole penetrating in a thickness direction, a core forming a closed magnetic path is arranged at a position including the through hole, the substrate is a multilayer substrate in which a plurality of constituent layers are stacked, the signal wiring includes a winding arranged around the through hole and a lead-out wiring connected to the winding in at least two of the plurality of constituent layers, the winding has one end connected to a first end lead-out wiring and the other end connected to a second end lead-out wiring in at least one of the at least two of the plurality of constituent layers, and the second end lead-out wiring is electrically connected to a housing made of a conductive material via a fastening member and is connected to the heat radiating wiring.

2. The electronic device according to claim 1, wherein the substrate is fixed on a housing made of a conductive material via a fastening member that is thermally connected to the heat radiating wiring.

3. The electronic device according to claim 1, wherein a heat radiating member is arranged between the substrate and the core.
 4. The electronic device according to claim 1, wherein the winding is located on both sides of the core in a normal direction with respect to a surface direction of the substrate, the heat radiating wiring is formed at a position including a periphery of the winding located on the both sides of the core in the normal direction, and the heat radiating wiring is divided into a region located on one side of the core and a region located on the other side of the core with respect to a virtual line passing through the winding and extending along one direction in the surface direction of the substrate.
 5. The electronic device according to claim 4, wherein the heat radiating wiring is divided into a region located on one side of the core and a region located on the other side of the core at a portion overlapping the core in the normal direction.
 6. The electronic device according to claim 1, wherein a connection area connecting the winding and the second end lead-out wiring is larger than a connection area connecting the winding and the first end lead-out wiring.
 7. The electronic device according to claim 1, wherein the substrate is arranged so that the other surface faces a housing made of a conductive material, and a heat radiating member thermally connected to the signal wiring is arranged on at least one of the one surface and the other surface of the substrate.
 8. The electronic device according to claim 7, wherein the heat radiating member is arranged on the one surface of the substrate, a pressing member is arranged on the heat radiating member, the substrate has a through hole penetrating in a thickness direction, a core forming a closed magnetic path is arranged at a position including the through hole, and the pressing member has a supporting portion arranged on the heat radiating member and a pressing portion integrally formed with the supporting portion to press the core.
 9. The electronic device according to claim 1, wherein the substrate is fixed on a housing at a plurality of locations via a fastening member, and a total thickness of a wiring including the signal wiring and the heat radiating wiring is a same among portions of the substrate pressed by the fastening member.
 10. The electronic device according to claim 1, wherein the substrate has a transformer configuration region in which the signal wiring and the heat radiating wiring are formed, and the heat radiating wiring is electrically connected to a housing made of a conductive material and is connected to a wiring outside the transformer configuration region.
 11. The electronic device according to claim 1, wherein the heat radiating wiring is divided into a plurality of regions in a normal direction with respect to a surface direction of the substrate, and the heat radiating wiring is divided into a region located on one side of the core and a region located on the other side of the core with respect to a virtual line passing through the winding and extending along one direction in the surface direction of the substrate.
-