

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12402135
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Khoshnevisan; Mostafa et al.

Feedback schemes for multiple component carrier scheduling and joint feedback reporting

Abstract

Methods, systems, and devices for wireless communications are described. A user equipment (UE) may receive, from a base station during a physical downlink control channel (PDCCH) monitoring occasion (PMO), first downlink control information (DCI) scheduling the UE for a first physical downlink shared channel (PDSCH) resource on a first component carrier and for a second PDSCH resource on a second component carrier. The UE may receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier. The UE may identify a set of downlink assignment indices (DAIs) for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers. The UE may transmit feedback based on the set of DAIs.

Inventors: Khoshnevisan; Mostafa (San Diego, CA), Takeda; Kazuki (Tokyo, JP), Xu; Huilin (Temecula, CA), Zhang; Xiaoxia (San Diego, CA)

Applicant: QUALCOMM Incorporated (San Diego, CA)

Family ID: 1000008777738

Assignee: QUALCOMM Incorporated (San Diego, CA)

Appl. No.: 17/375092

Filed: July 14, 2021

Prior Publication Data

Document Identifier	Publication Date
US 20220022235 A1	Jan. 20, 2022

Related U.S. Application Data

Publication Classification

Int. Cl.: **H04W72/23** (20230101); **H04L1/1812** (20230101); **H04L1/1867** (20230101);
H04W24/08 (20090101); **H04W72/0446** (20230101); **H04W72/0453** (20230101);
H04W72/1263 (20230101)

U.S. Cl.:

CPC **H04W72/23** (20230101); **H04L1/1819** (20130101); **H04L1/1896** (20130101);
H04W24/08 (20130101); **H04W72/0446** (20130101); **H04W72/0453** (20130101);
H04W72/1263 (20130101);

Field of Classification Search

CPC: H04W (72/23); H04W (24/08); H04W (72/0446); H04W (72/0453); H04W (72/1263);
H04L (1/1819); H04L (1/1896); H04L (1/1864); H04L (5/0091); H04L (5/0055); H04L
(5/001)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2011/0170496	12/2010	Fong	370/329	H04W 52/24
2012/0294694	12/2011	Garot	411/427	F27D 1/141
2020/0015229	12/2019	Yang et al.	N/A	N/A
2020/0092068	12/2019	Yang et al.	N/A	N/A
2020/0145984	12/2019	Hosseini et al.	N/A	N/A
2022/0052824	12/2021	Kim	N/A	H04L 1/0027
2022/0240228	12/2021	Matsumura	N/A	H04L 1/1861
2022/0272733	12/2021	Gou	N/A	H04W 72/1273

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
110535573	12/2018	CN	N/A
WO-2016162090	12/2015	WO	N/A

OTHER PUBLICATIONS

International Search Report and Written Opinion—PCT/US2021/041756—ISA/EPO—Feb. 11, 2022 (206296WO). cited by applicant

Xiaomi: “Enhancements on Multi-TRP/Panel Transmission”, 3GPP Draft, R1-1912994, 3GPP TSG RAN WG1 #99, 3rd Generation Partnership Project (3GPP), Mobile Competence Centre, 650, Route Des Lucioles, F-06921 Sophia-Antipolis Cedex, France, vol. RAN WG1, No. Reno, USA, Nov. 18, 2019-Nov. 22, 2019, Nov. 8, 2019 (Nov. 8, 2019), XP051820251, 4 Pages, Retrieved from the Internet: URL:https://ftp.3gpp.org/tsg_ran/WG1_RL1/TSGR1_99/Docs/R1-1912994.zip, R1-1912994.docx [retrieved on Nov. 8, 2019] section 3.1. cited by applicant

Background/Summary

CROSS REFERENCE (1) The present application for patent claims the benefit of U.S. Provisional Patent Application No. 63/053,495 by KHOSHNEVISAN et al., entitled “FEEDBACK SCHEMES FOR MULTIPLE COMPONENT CARRIER SCHEDULING AND JOINT FEEDBACK REPORTING,” filed Jul. 17, 2020, assigned to the assignee hereof, and expressly incorporated by reference herein.

FIELD OF TECHNOLOGY

(1) The following relates to wireless communications, including feedback schemes for multiple component carrier scheduling and joint feedback reporting.

BACKGROUND

(2) Wireless communications systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). Examples of such multiple-access systems include fourth generation (4G) systems such as Long Term Evolution (LTE) systems, LTE-Advanced (LTE-A) systems, or LTE-A Pro systems, and fifth generation (5G) systems which may be referred to as New Radio (NR) systems. These systems may employ technologies such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal frequency division multiple access (OFDMA), or discrete Fourier transform spread orthogonal frequency division multiplexing (DFT-S-OFDM). A wireless multiple-access communications system may include one or more base stations or one or more network access nodes, each simultaneously supporting communication for multiple communication devices, which may be otherwise known as user equipment (UE).

(3) A UE may be scheduled for data communications in one or more component carriers by one or more downlink control information (DCI) instances. Some techniques for providing feedback when the UE is scheduled in multi-component carrier or cross-component carrier schemes can be improved.

SUMMARY

(4) The described techniques relate to improved methods, systems, devices, and apparatuses that support feedback schemes for multiple component carrier scheduling and joint feedback reporting. A user equipment (UE) may receive two downlink control information (DCI) in one physical downlink control channel (PDCCH) monitoring occasion (PMO), each DCI scheduling the UE for different physical downlink shared channel (PDSCH) resources on a same component carrier. In some examples, the UE may receive one DCI scheduling two PDSCHs in different component carriers. In some cases, the UE may be scheduled according to both of these examples at the same time. For example, a UE may receive at least two DCI in a PMO, where a first DCI schedules the UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier, and a second DCI schedules the UE for a third PDSCH resource on the first component carrier or the second component carrier. The techniques described herein support generating feedback for scheduling techniques where, during a PMO, a UE is scheduled for PDSCH resources on multiple component carriers by a single DCI and, during the PMO, the UE is scheduled for multiple PDSCH resources on a single component carrier.

(5) Additional techniques are described herein to support providing joint feedback for multiple

PDSCH resources corresponding to different control resource set (CORESET) pool indices. The multiple PDSCH resources for the different CORESET pool indices may be scheduled for the same component carrier during the same PMO. The UE may generate a hybrid automatic repeat request (HARQ) acknowledgement (ACK) codebook for the PDSCH resources corresponding to the different CORESET pool indices and report the feedback on an uplink control channel. In some examples, the different CORESET pool indices may correspond to different transmission and reception points (TRPs).

(6) A method for wireless communications at a UE is described. The method may include receiving, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier, receiving, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier, identifying a set of downlink assignment indices (DAIs) for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and transmitting feedback based on the set of DAIs.

(7) An apparatus for wireless communications at a UE is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory. The instructions may be executable by the processor to cause the apparatus to receive, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier, receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier, identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and transmit feedback based on the set of DAIs.

(8) Another apparatus for wireless communications at a UE is described. The apparatus may include means for receiving, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier, means for receiving, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier, means for identifying a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and means for transmitting feedback based on the set of DAIs.

(9) A non-transitory computer-readable medium storing code for wireless communications at a UE is described. The code may include instructions executable by a processor to receive, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier, receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier, identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and transmit feedback based on the set of DAIs.

(10) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining a first associated component carrier index for the first DCI based on a highest component carrier index of the first component carrier and the second component carrier.

(11) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining a first associated component carrier index for the first DCI based on a lowest component carrier index of the first component carrier and the second component carrier.

(12) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or

instructions for determining that a first associated component carrier index for the first DCI and a second associated component carrier index for the second DCI may be a same associated component carrier index based on the second PDSCH resource and the third PDSCH resource being scheduled on the second component carrier, and determining a first DAI for the first DCI and a second DAI for the second DCI based on a time domain order of the second PDSCH resource and the third PDSCH resource.

(13) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining a first DAI for the first DCI corresponds to a first component carrier index associated with the first component carrier based on the first PDSCH resource, and determining a second DAI for the second DCI corresponds to a second component carrier index associated with the second component carrier based on the third PDSCH resource.

(14) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining a first DAI for the first DCI associated with the first component carrier and the first PDSCH resource, determining a second DAI for the first DCI associated with the second component carrier and the second PDSCH resource, and determining a third DAI for the second DCI associated with the second component carrier and the third PDSCH resource.

(15) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the second DAI and the third DAI may be based on a temporal ordering of the second PDSCH resource and the third PDSCH resource.

(16) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for receiving, during the PMO, a third DCI scheduling the UE for a fourth PDSCH resource on the first component carrier.

(17) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining a fourth DAI for the third DCI associated with the first component carrier and the fourth PDSCH resource, where the fourth DAI and the first DAI may be based on a temporal ordering of the first PDSCH resource and the fourth PDSCH resource.

(18) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for generating a HARQ ACK codebook whose order may be based on the set of DAIs.

(19) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for determining a set of ACK or negative ACK (NACK) bits for each DAI of the set of DAIs.

(20) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for determining feedback values for the set of ACK or NACK bits of a first DAI associated with the first DCI based on the first DCI scheduling a set of PDSCH resources, each of the set of ACK or NACK bits of the first DAI corresponding to a different one of the first PDSCH resource and the second PDSCH resource.

(21) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for determining a first feedback value for a first bit of the set of ACK or NACK bits of a second DAI associated with the second DCI based on the second DCI scheduling a single PDSCH resource, and including a NACK for a second bit of the set of ACK or NACK bits of the second DAI associated with the second DCI.

(22) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the set of DAIs may be ordered first based on ascending order of an associated

serving cell index with DCI in a given PMO then based at last in part on ascending order of PMO index.

(23) A method for wireless communications at a base station is described. The method may include transmitting, during a PMO, a first DCI scheduling a UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier, transmitting, during the PMO, a second DCI scheduling the UE for a third PDSCH resource on the second component carrier, receiving feedback for at least the first PDSCH resource, the second PDSCH resource, and the third PDSCH resource on a physical uplink control channel (PUCCH), identifying a set of DAIS for the first DCI and the second DCI, where the first DCI has one or more DAIS whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and decoding the feedback based on the set of DAIS.

(24) An apparatus for wireless communications at a base station is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory. The instructions may be executable by the processor to cause the apparatus to transmit, during a PMO, a first DCI scheduling a UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier, transmit, during the PMO, a second DCI scheduling the UE for a third PDSCH resource on the second component carrier, receive feedback for at least the first PDSCH resource, the second PDSCH resource, and the third PDSCH resource on a PUCCH, identify a set of DAIS for the first DCI and the second DCI, where the first DCI has one or more DAIS whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and decode the feedback based on the set of DAIS.

(25) Another apparatus for wireless communications at a base station is described. The apparatus may include means for transmitting, during a PMO, a first DCI scheduling a UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier, means for transmitting, during the PMO, a second DCI scheduling the UE for a third PDSCH resource on the second component carrier, means for receiving feedback for at least the first PDSCH resource, the second PDSCH resource, and the third PDSCH resource on a PUCCH, means for identifying a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and means for decoding the feedback based on the set of DAIs.

(26) A non-transitory computer-readable medium storing code for wireless communications at a base station is described. The code may include instructions executable by a processor to transmit, during a PMO, a first DCI scheduling a UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier, transmit, during the PMO, a second DCI scheduling the UE for a third PDSCH resource on the second component carrier, receive feedback for at least the first PDSCH resource, the second PDSCH resource, and the third PDSCH resource on a PUCCH, identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and decode the feedback based on the set of DAIs.

(27) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining a first associated component carrier index for the first DCI based on a highest component carrier index of the first component carrier and the second component carrier.

(28) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining a first associated component carrier index for the first DCI based on a lowest component carrier index of the first component carrier and the second component carrier.

(29) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or

instructions for determining a first associated component carrier index for the first DCI and a second associated component carrier index for the second DCI may be a same associated component carrier index based on the second PDSCH resource and the third PDSCH resource being scheduled on the second component carrier, and determining a first DAI for the first DCI and a second DAI for the second DCI based on a time domain order of the second PDSCH resource and the third PDSCH resource, where the feedback may be decoded based on the first DAI and the second DAI.

(30) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining a first DAI for the first DCI corresponds to a first component carrier index associated with the first component carrier based on the first PDSCH resource, and determining a second DAI for the second DCI corresponds to a second component carrier index associated with the second component carrier based on the third PDSCH resource, where the feedback may be decoded based on the first DAI and the second DAI.

(31) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for determining a first DAI for the first DCI associated with the first component carrier and the first PDSCH resource, determining a second DAI for the first DCI associated with the second component carrier and the second PDSCH resource, and determining a third DAI for the second DCI associated with the second component carrier and the third PDSCH resource, where the feedback may be decoded based on the first DAI, the second DAI, and the third DAI.

(32) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the second DAI and the third DAI may be based on a temporal ordering of the second PDSCH resource and the third PDSCH resource.

(33) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for transmitting, during the PMO, a third DCI scheduling the UE for a fourth PDSCH resource on the first component carrier.

(34) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining a fourth DAI for the third DCI associated with the first component carrier and the fourth PDSCH resource, where the fourth DAI and the first DAI may be based on a temporal ordering of the first PDSCH resource and the fourth PDSCH resource, and where the feedback may be decoded based on the fourth DAI.

(35) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the feedback includes a HARQ ACK codebook whose order may be generated based on the set of DAIs.

(36) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the feedback includes a set of ACK or NACK bits for each DAI of the set of DAIs.

(37) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, decoding the feedback may include operations, features, means, or instructions for identifying feedback values for the set of ACK or NACK bits of a first DAI associated with the first DCI based on the first DCI scheduling a set of PDSCH resources, each of the set of ACK or NACK bits of the first DAI corresponding to a different one of the first PDSCH resource and the second PDSCH resource.

(38) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, decoding the feedback may include operations, features, means, or instructions for identifying a first feedback value for a first bit of the set of ACK or NACK bits of a second DAI associated with the second DCI based on the second DCI scheduling a single PDSCH resource, and

identifying a NACK for a second bit of the set of ACK or NACK bits of the second DAI associated with the second DCI.

(39) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the set of DAIs may be ordered first based on ascending order of an associated serving cell index with DCI in a corresponding PMO then based at last in part on ascending order of PMO index.

(40) A method for wireless communications at a UE is described. The method may include receiving, from a base station during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, receiving, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, identifying a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and transmitting feedback based on the set of DAIs.

(41) An apparatus for wireless communications at a UE is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory. The instructions may be executable by the processor to cause the apparatus to receive, from a base station during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, receive, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and transmit feedback based on the set of DAIs.

(42) Another apparatus for wireless communications at a UE is described. The apparatus may include means for receiving, from a base station during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, means for receiving, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, means for identifying a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and means for transmitting feedback based on the set of DAIs.

(43) A non-transitory computer-readable medium storing code for wireless communications at a UE is described. The code may include instructions executable by a processor to receive, from a base station during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, receive, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and transmit feedback based on the set of DAIs.

(44) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for transmitting, to

a base station, a UE capability associated with a number of PDSCH resources per PMO per cell, the number of PDSCH resources per PMO per cell, or both.

(45) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining an ordering for the set of DAIs based on a temporal ordering of the PDSCH resources associated with a same CORESET pool index on the same component carrier scheduled during the PMO, then based on a CORESET pool index ordering on the same component carrier scheduled during the PMO, then based on a component carrier index ordering for the PMO, then based on a PMO ordering.

(46) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining an ordering for the set of DAIs based on a CORESET pool index ordering for the PDSCH resources having a common starting resource in a time domain on the same common component carrier scheduled during the PMO, then based on a temporal ordering of the PDSCH resources on the same component carrier scheduled during the PMO, then based on a component carrier index ordering for component carriers scheduled during the PMO, then based on a PMO index ordering.

(47) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the one or more first DCI and the one or more second DCI include up to a maximum number of DCI.

(48) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the maximum number of DCI may be twice a value indicated by the UE.

(49) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the maximum number of DCI may be indicated by the UE, where a first PDSCH resource and a second PDSCH resource may have a same starting resource in a time domain.

(50) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for determining the one or more first DCI allocate one or more third PDSCH resources in a second component carrier.

(51) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first CORESET pool index corresponds to a first TRP, and the second CORESET pool index corresponds to a second TRP.

(52) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, an ordering for the set of DAIs may be based on a PDSCH resource start time ordering, a CORESET pool index ordering, a component carrier index ordering, a PMO index ordering, or any combination thereof.

(53) A method for wireless communications at a base station is described. The method may include transmitting, to a UE during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, transmitting, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, receiving feedback for the one or more first PDSCH resources and the one or more second PDSCH resources on a PUCCH, identifying a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and decoding the feedback based on the set of DAIs.

(54) An apparatus for wireless communications at a base station is described. The apparatus may include a processor, memory in electronic communication with the processor, and instructions stored in the memory. The instructions may be executable by the processor to cause the apparatus

to transmit, to a UE during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, transmit, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, receive feedback for the one or more first PDSCH resources and the one or more second PDSCH resources on a PUCCH, identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and decode the feedback based on the set of DAIs.

(55) Another apparatus for wireless communications at a base station is described. The apparatus may include means for transmitting, to a UE during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, means for transmitting, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, means for receiving feedback for the one or more first PDSCH resources and the one or more second PDSCH resources on a PUCCH, means for identifying a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and means for decoding the feedback based on the set of DAIs.

(56) A non-transitory computer-readable medium storing code for wireless communications at a base station is described. The code may include instructions executable by a processor to transmit, to a UE during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, transmit, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, receive feedback for the one or more first PDSCH resources and the one or more second PDSCH resources on a PUCCH, identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and decode the feedback based on the set of DAIs.

(57) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for receiving, from the UE, a UE capability associated with a number of PDSCH resources per PMO per cell, the number of PDSCH resources per PMO per cell, or both.

(58) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining an ordering for the set of DAIs based on a temporal ordering of the PDSCH resources associated with a same CORESET pool index on the same component carrier scheduled during the PMO, then based on a CORESET pool index ordering on the same component carrier scheduled during the PMO, then based on a component carrier index ordering for the PMO, then based on a PMO ordering.

(59) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, identifying the set of DAIs further may include operations, features, means, or instructions for determining an ordering for the set of DAIs based on a CORESET pool index ordering for the PDSCH resources having a common starting resource in a time domain on the same common component carrier scheduled during the PMO, then based on a temporal ordering of

the PDSCH resources on the same component carrier scheduled during the PMO, then based on a component carrier index ordering for component carriers scheduled during the PMO, then based on a PMO index ordering.

(60) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the one or more first DCI and the one or more second DCI include up to a maximum number of DCI instances based.

(61) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the maximum number of DCI may be twice a value indicated by the UE.

(62) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the maximum number of DCI may be indicated by the UE, where a first PDSCH resource and a second PDSCH resource may have a same starting resource in a time domain.

(63) Some examples of the method, apparatuses, and non-transitory computer-readable medium described herein may further include operations, features, means, or instructions for determining the one or more first DCI allocate one or more third PDSCH resources on a second component carrier.

(64) In some examples of the method, apparatuses, and non-transitory computer-readable medium described herein, the first CORESET pool index corresponds to a first TRP, and the second CORESET pool index corresponds to a second TRP.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIGS. 1 and 2 illustrate examples of wireless communications systems that support feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(2) FIGS. 3 through 5 illustrate examples of scheduling schemes that support feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(3) FIGS. 6 and 7 illustrate examples of joint feedback reporting schemes that support feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(4) FIGS. 8 and 9 illustrate examples of process flows that support feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(5) FIGS. 10 and 11 show block diagrams of devices that support feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(6) FIG. 12 shows a block diagram of a communication manager that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(7) FIG. 13 shows a diagram of a system including a device that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(8) FIGS. 14 and 15 show block diagrams of devices that support feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(9) FIG. 16 shows a block diagram of a communication manager that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(10) FIG. 17 shows a diagram of a system including a device that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

(11) FIGS. 18 through 23 show flowcharts illustrating methods that support feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure.

DETAILED DESCRIPTION

(12) A user equipment (UE) may communicate with a base station on multiple component carriers. The base station may transmit downlink control information (DCI) to schedule the UE for physical downlink shared channel (PDSCH) resources on one or more of the component carriers for a data transmission to the UE. The DCI may be transmitted to the UE during a physical downlink control channel (PDCCH) monitoring occasion (PMO), and the base station may transmit one or more DCI in one or more component carriers per-PMO to schedule the UE for one or more PDSCH resources. In some cases, the UE may be configured to report hybrid automatic repeat request (HARQ) acknowledgement (ACK) feedback for multiple PDSCH resources. For example, the UE may generate a HARQ ACK codebook, where indices of the codebook correspond to ACK or negative ACK (NACK) feedback for scheduled PDSCH resources. The ordering of the codebook may be based on downlink assignment indicator (DAI) values, which may be indicated by or correspond to DCI which schedule the PDSCH resources. A value of a DAI field in DCI may denote an accumulative number of serving cell and PMO pairs in which PDSCH reception is present up to the current serving cell and current PMO. The DAI may increment first in an ascending order of serving cell index, then in ascending order of PMO index.

(13) UEs described herein may support multiple different techniques for PDSCH resource scheduling. In some examples, a UE may receive two DCI in one PMO, each DCI scheduling the UE for different PDSCH resources on a same component carrier. In some examples, a UE may receive one DCI scheduling two PDSCHs in different component carriers. In some cases, the UE may be scheduled according to both of these examples at the same time. For example, a UE may receive at least two DCI in a PMO, where a first DCI schedules the UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier, and a second DCI schedules the UE for a third PDSCH resource on the first component carrier or the second component carrier. The techniques described herein support generating feedback for scheduling techniques where, during a PMO, a UE is scheduled for PDSCH resources on multiple component carriers by a single DCI and, during the PMO, the UE is scheduled for multiple PDSCH resources on a single component carrier.

(14) Additional techniques are described herein to support providing joint feedback for multiple PDSCH resources corresponding to different control resource set (CORESET) pool indices. The multiple PDSCH resources for the different CORESET pool indices may be scheduled for the same component carrier during the same PMO. The UE may generate a HARQ ACK codebook for the PDSCH resources corresponding to the different CORESET pool indices and report the feedback on an uplink control channel. In some examples, the different CORESET pool indices may correspond to different transmission and reception points (TRPs). The described techniques may enable the UE to transmit HARQ ACK feedback with improved efficiency and reduced processing costs, among other benefits.

(15) Aspects of the disclosure are initially described in the context of wireless communications systems. Aspects of the disclosure are further illustrated by and described with reference to apparatus diagrams, system diagrams, and flowcharts that relate to feedback schemes for multiple component carrier scheduling and joint feedback reporting.

(16) FIG. 1 illustrates an example of a wireless communications system 100 that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The wireless communications system 100 may include one or

more base stations **105**, one or more UEs **115**, and a core network **130**. In some examples, the wireless communications system **100** may be a Long Term Evolution (LTE) network, an LTE-Advanced (LTE-A) network, an LTE-A Pro network, or a New Radio (NR) network. In some examples, the wireless communications system **100** may support enhanced broadband communications, ultra-reliable (e.g., mission critical) communications, low latency communications, communications with low-cost and low-complexity devices, or any combination thereof.

(17) The base stations **105** may be dispersed throughout a geographic area to form the wireless communications system **100** and may be devices in different forms or having different capabilities. The base stations **105** and the UEs **115** may wirelessly communicate via one or more communication links **125**. Each base station **105** may provide a coverage area **110** over which the UEs **115** and the base station **105** may establish one or more communication links **125**. The coverage area **110** may be an example of a geographic area over which a base station **105** and a UE **115** may support the communication of signals according to one or more radio access technologies.

(18) The UEs **115** may be dispersed throughout a coverage area **110** of the wireless communications system **100**, and each UE **115** may be stationary, or mobile, or both at different times. The UEs **115** may be devices in different forms or having different capabilities. Some example UEs **115** are illustrated in FIG. 1. The UEs **115** described herein may be able to communicate with various types of devices, such as other UEs **115**, the base stations **105**, or network equipment (e.g., core network nodes, relay devices, integrated access and backhaul (IAB) nodes, or other network equipment), as shown in FIG. 1.

(19) The base stations **105** may communicate with the core network **130**, or with one another, or both. For example, the base stations **105** may interface with the core network **130** through one or more backhaul links **120** (e.g., via an S1, N2, N3, or other interface). The base stations **105** may communicate with one another over the backhaul links **120** (e.g., via an X2, Xn, or other interface) either directly (e.g., directly between base stations **105**), or indirectly (e.g., via core network **130**), or both. In some examples, the backhaul links **120** may be or include one or more wireless links.

(20) One or more of the base stations **105** described herein may include or may be referred to by a person having ordinary skill in the art as a base transceiver station, a radio base station, an access point, a radio transceiver, a NodeB, an eNodeB (eNB), a next-generation NodeB or a giga-NodeB (either of which may be referred to as a gNB), a Home NodeB, a Home eNodeB, or other suitable terminology.

(21) A UE **115** may include or may be referred to as a mobile device, a wireless device, a remote device, a handheld device, or a subscriber device, or some other suitable terminology, where the “device” may also be referred to as a unit, a station, a terminal, or a client, among other examples. A UE **115** may also include or may be referred to as a personal electronic device such as a cellular phone, a personal digital assistant (PDA), a tablet computer, a laptop computer, or a personal computer. In some examples, a UE **115** may include or be referred to as a wireless local loop (WLL) station, an Internet of Things (IoT) device, an Internet of Everything (IoE) device, or a machine type communications (MTC) device, among other examples, which may be implemented in various objects such as appliances, or vehicles, meters, among other examples.

(22) The UEs **115** described herein may be able to communicate with various types of devices, such as other UEs **115** that may sometimes act as relays as well as the base stations **105** and the network equipment including macro eNBs or gNBs, small cell eNBs or gNBs, or relay base stations, among other examples, as shown in FIG. 1.

(23) The UEs **115** and the base stations **105** may wirelessly communicate with one another via one or more communication links **125** over one or more carriers. The term “carrier” may refer to a set of radio frequency spectrum resources having a defined physical layer structure for supporting the communication links **125**. For example, a carrier used for a communication link **125** may include a portion of a radio frequency spectrum band (e.g., a bandwidth part (BWP)) that is operated

according to one or more physical layer channels for a given radio access technology (e.g., LTE, LTE-A, LTE-A Pro, NR). Each physical layer channel may carry acquisition signaling (e.g., synchronization signals, system information), control signaling that coordinates operation for the carrier, user data, or other signaling. The wireless communications system **100** may support communication with a UE **115** using carrier aggregation or multi-carrier operation. A UE **115** may be configured with multiple downlink component carriers and one or more uplink component carriers according to a carrier aggregation configuration. Carrier aggregation may be used with both frequency division duplexing (FDD) and time division duplexing (TDD) component carriers. (24) In some examples (e.g., in a carrier aggregation configuration), a carrier may also have acquisition signaling or control signaling that coordinates operations for other carriers. A carrier may be associated with a frequency channel (e.g., an evolved universal mobile telecommunication system terrestrial radio access (E-UTRA) absolute radio frequency channel number (EARFCN)) and may be positioned according to a channel raster for discovery by the UEs **115**. A carrier may be operated in a standalone mode where initial acquisition and connection may be conducted by the UEs **115** via the carrier, or the carrier may be operated in a non-standalone mode where a connection is anchored using a different carrier (e.g., of the same or a different radio access technology).

(25) The communication links **125** shown in the wireless communications system **100** may include uplink transmissions from a UE **115** to a base station **105**, or downlink transmissions from a base station **105** to a UE **115**. Carriers may carry downlink or uplink communications (e.g., in an FDD mode) or may be configured to carry downlink and uplink communications (e.g., in a TDD mode).

(26) A carrier may be associated with a particular bandwidth of the radio frequency spectrum, and in some examples the carrier bandwidth may be referred to as a “system bandwidth” of the carrier or the wireless communications system **100**. For example, the carrier bandwidth may be one of a number of determined bandwidths for carriers of a particular radio access technology (e.g., 1.4, 3, 5, 10, 15, 20, 40, or 80 megahertz (MHz)). Devices of the wireless communications system **100** (e.g., the base stations **105**, the UEs **115**, or both) may have hardware configurations that support communications over a particular carrier bandwidth or may be configurable to support communications over one of a set of carrier bandwidths. In some examples, the wireless communications system **100** may include base stations **105** or UEs **115** that support simultaneous communications via carriers associated with multiple carrier bandwidths. In some examples, each served UE **115** may be configured for operating over portions (e.g., a sub-band, a BWP) or all of a carrier bandwidth.

(27) Signal waveforms transmitted over a carrier may be made up of multiple subcarriers (e.g., using multi-carrier modulation (MCM) techniques such as orthogonal frequency division multiplexing (OFDM) or discrete Fourier transform spread OFDM (DFT-S-OFDM)). In a system employing MCM techniques, a resource element may consist of one symbol period (e.g., a duration of one modulation symbol) and one subcarrier, where the symbol period and subcarrier spacing are inversely related. The number of bits carried by each resource element may depend on the modulation scheme (e.g., the order of the modulation scheme, the coding rate of the modulation scheme, or both). Thus, the more resource elements that a UE **115** receives and the higher the order of the modulation scheme, the higher the data rate may be for the UE **115**. A wireless communications resource may refer to a combination of a radio frequency spectrum resource, a time resource, and a spatial resource (e.g., spatial layers or beams), and the use of multiple spatial layers may further increase the data rate or data integrity for communications with a UE **115**.

(28) One or more numerologies for a carrier may be supported, where a numerology may include a subcarrier spacing (Δf) and a cyclic prefix. A carrier may be divided into one or more BWPs having the same or different numerologies. In some examples, a UE **115** may be configured with multiple BWPs. In some examples, a single BWP for a carrier may be active at a given time and communications for the UE **115** may be restricted to one or more active BWPs.

(29) The time intervals for the base stations **105** or the UEs **115** may be expressed in multiples of a basic time unit which may, for example, refer to a sampling period of $T_{\text{sub.s}} = 1/(\Delta f_{\text{sub.max}} \cdot N_{\text{sub.f}})$ seconds, where $\Delta f_{\text{sub.max}}$ may represent the maximum supported subcarrier spacing, and $N_{\text{sub.f}}$ may represent the maximum supported discrete Fourier transform (DFT) size. Time intervals of a communications resource may be organized according to radio frames each having a specified duration (e.g., 10 milliseconds (ms)). Each radio frame may be identified by a system frame number (SFN) (e.g., ranging from 0 to 1023).

(30) Each frame may include multiple consecutively numbered subframes or slots, and each subframe or slot may have the same duration. In some examples, a frame may be divided (e.g., in the time domain) into subframes, and each subframe may be further divided into a number of slots. Alternatively, each frame may include a variable number of slots, and the number of slots may depend on subcarrier spacing. Each slot may include a number of symbol periods (e.g., depending on the length of the cyclic prefix prepended to each symbol period). In some wireless communications systems **100**, a slot may further be divided into multiple mini-slots containing one or more symbols. Excluding the cyclic prefix, each symbol period may contain one or more (e.g., $N_{\text{sub.f}}$) sampling periods. The duration of a symbol period may depend on the subcarrier spacing or frequency band of operation.

(31) A subframe, a slot, a mini-slot, or a symbol may be the smallest scheduling unit (e.g., in the time domain) of the wireless communications system **100** and may be referred to as a transmission time interval (TTI). In some examples, the TTI duration (e.g., the number of symbol periods in a TTI) may be variable. Additionally or alternatively, the smallest scheduling unit of the wireless communications system **100** may be dynamically selected (e.g., in bursts of shortened TTIs (sTTIs)).

(32) Physical channels may be multiplexed on a carrier according to various techniques. A physical control channel and a physical data channel may be multiplexed on a downlink carrier, for example, using one or more of time division multiplexing (TDM) techniques, frequency division multiplexing (FDM) techniques, or hybrid TDM-FDM techniques. A control region (e.g., a CORESET) for a physical control channel may be defined by a number of symbol periods and may extend across the system bandwidth or a subset of the system bandwidth of the carrier. One or more control regions (e.g., CORESETs) may be configured for a set of the UEs **115**. For example, one or more of the UEs **115** may monitor or search control regions for control information according to one or more search space sets, and each search space set may include one or multiple control channel candidates in one or more aggregation levels arranged in a cascaded manner. An aggregation level for a control channel candidate may refer to a number of control channel resources (e.g., control channel elements (CCEs)) associated with encoded information for a control information format having a given payload size. Search space sets may include common search space sets configured for sending control information to multiple UEs **115** and UE-specific search space sets for sending control information to a specific UE **115**.

(33) Each base station **105** may provide communication coverage via one or more cells, for example a macro cell, a small cell, a hot spot, or other types of cells, or any combination thereof. The term “cell” may refer to a logical communication entity used for communication with a base station **105** (e.g., over a carrier) and may be associated with an identifier for distinguishing neighboring cells (e.g., a physical cell identifier (PCID), a virtual cell identifier (VCID), or others). In some examples, a cell may also refer to a geographic coverage area **110** or a portion of a geographic coverage area **110** (e.g., a sector) over which the logical communication entity operates. Such cells may range from smaller areas (e.g., a structure, a subset of structure) to larger areas depending on various factors such as the capabilities of the base station **105**. For example, a cell may be or include a building, a subset of a building, or exterior spaces between or overlapping with geographic coverage areas **110**, among other examples.

(34) A macro cell generally covers a relatively large geographic area (e.g., several kilometers in

radius) and may allow unrestricted access by the UEs **115** with service subscriptions with the network provider supporting the macro cell. A small cell may be associated with a lower-powered base station **105**, as compared with a macro cell, and a small cell may operate in the same or different (e.g., licensed, unlicensed) frequency bands as macro cells. Small cells may provide unrestricted access to the UEs **115** with service subscriptions with the network provider or may provide restricted access to the UEs **115** having an association with the small cell (e.g., the UEs **115** in a closed subscriber group (CSG), the UEs **115** associated with users in a home or office). A base station **105** may support one or multiple cells and may also support communications over the one or more cells using one or multiple component carriers.

(35) In some examples, a carrier may support multiple cells, and different cells may be configured according to different protocol types (e.g., MTC, narrowband IoT (NB-IoT), enhanced mobile broadband (eMBB)) that may provide access for different types of devices.

(36) In some examples, a base station **105** may be movable and therefore provide communication coverage for a moving geographic coverage area **110**. In some examples, different geographic coverage areas **110** associated with different technologies may overlap, but the different geographic coverage areas **110** may be supported by the same base station **105**. In other examples, the overlapping geographic coverage areas **110** associated with different technologies may be supported by different base stations **105**. The wireless communications system **100** may include, for example, a heterogeneous network in which different types of the base stations **105** provide coverage for various geographic coverage areas **110** using the same or different radio access technologies.

(37) The wireless communications system **100** may support synchronous or asynchronous operation. For synchronous operation, the base stations **105** may have similar frame timings, and transmissions from different base stations **105** may be approximately aligned in time. For asynchronous operation, the base stations **105** may have different frame timings, and transmissions from different base stations **105** may, in some examples, not be aligned in time. The techniques described herein may be used for either synchronous or asynchronous operations.

(38) Some UEs **115**, such as MTC or IoT devices, may be low cost or low complexity devices and may provide for automated communication between machines (e.g., via Machine-to-Machine (M2M) communication). M2M communication or MTC may refer to data communication technologies that allow devices to communicate with one another or a base station **105** without human intervention. In some examples, M2M communication or MTC may include communications from devices that integrate sensors or meters to measure or capture information and relay such information to a central server or application program that makes use of the information or presents the information to humans interacting with the application program. Some UEs **115** may be designed to collect information or enable automated behavior of machines or other devices. Examples of applications for MTC devices include smart metering, inventory monitoring, water level monitoring, equipment monitoring, healthcare monitoring, wildlife monitoring, weather and geological event monitoring, fleet management and tracking, remote security sensing, physical access control, and transaction-based business charging.

(39) Some UEs **115** may be configured to employ operating modes that reduce power consumption, such as half-duplex communications (e.g., a mode that supports one-way communication via transmission or reception, but not transmission and reception simultaneously). In some examples, half-duplex communications may be performed at a reduced peak rate. Other power conservation techniques for the UEs **115** include entering a power saving deep sleep mode when not engaging in active communications, operating over a limited bandwidth (e.g., according to narrowband communications), or a combination of these techniques. For example, some UEs **115** may be configured for operation using a narrowband protocol type that is associated with a defined portion or range (e.g., set of subcarriers or resource blocks (RBs)) within a carrier, within a guard-band of a carrier, or outside of a carrier.

(40) The wireless communications system **100** may be configured to support ultra-reliable communications or low-latency communications, or various combinations thereof. For example, the wireless communications system **100** may be configured to support ultra-reliable low-latency communications (URLLC) or mission critical communications. The UEs **115** may be designed to support ultra-reliable, low-latency, or critical functions (e.g., mission critical functions). Ultra-reliable communications may include private communication or group communication and may be supported by one or more mission critical services such as mission critical push-to-talk (MCPTT), mission critical video (MCVideo), or mission critical data (MCData). Support for mission critical functions may include prioritization of services, and mission critical services may be used for public safety or general commercial applications. The terms ultra-reliable, low-latency, mission critical, and ultra-reliable low-latency may be used interchangeably herein.

(41) In some examples, a UE **115** may also be able to communicate directly with other UEs **115** over a device-to-device (D2D) communication link **135** (e.g., using a peer-to-peer (P2P) or D2D protocol). One or more UEs **115** utilizing D2D communications may be within the geographic coverage area **110** of a base station **105**. Other UEs **115** in such a group may be outside the geographic coverage area **110** of a base station **105** or be otherwise unable to receive transmissions from a base station **105**. In some examples, groups of the UEs **115** communicating via D2D communications may utilize a one-to-many (1:M) system in which each UE **115** transmits to every other UE **115** in the group. In some examples, a base station **105** facilitates the scheduling of resources for D2D communications. In other cases, D2D communications are carried out between the UEs **115** without the involvement of a base station **105**.

(42) In some systems, the D2D communication link **135** may be an example of a communication channel, such as a sidelink communication channel, between vehicles (e.g., UEs **115**). In some examples, vehicles may communicate using vehicle-to-everything (V2X) communications, vehicle-to-vehicle (V2V) communications, or some combination of these. A vehicle may signal information related to traffic conditions, signal scheduling, weather, safety, emergencies, or any other information relevant to a V2X system. In some examples, vehicles in a V2X system may communicate with roadside infrastructure, such as roadside units, or with the network via one or more network nodes (e.g., base stations **105**) using vehicle-to-network (V2N) communications, or with both.

(43) The core network **130** may provide user authentication, access authorization, tracking, Internet Protocol (IP) connectivity, and other access, routing, or mobility functions. The core network **130** may be an evolved packet core (EPC) or 5G core (5GC), which may include at least one control plane entity that manages access and mobility (e.g., a mobility management entity (MME), an access and mobility management function (AMF)) and at least one user plane entity that routes packets or interconnects to external networks (e.g., a serving gateway (S-GW), a Packet Data Network (PDN) gateway (P-GW), or a user plane function (UPF)). The control plane entity may manage non-access stratum (NAS) functions such as mobility, authentication, and bearer management for the UEs **115** served by the base stations **105** associated with the core network **130**. User IP packets may be transferred through the user plane entity, which may provide IP address allocation as well as other functions. The user plane entity may be connected to the network operators IP services **150**. The operators IP services **150** may include access to the Internet, Intranet(s), an IP Multimedia Subsystem (IMS), or a Packet-Switched Streaming Service.

(44) Some of the network devices, such as a base station **105**, may include subcomponents such as an access network entity **140**, which may be an example of an access node controller (ANC). Each access network entity **140** may communicate with the UEs **115** through one or more other access network transmission entities **145**, which may be referred to as radio heads, smart radio heads, or TRPs. Each access network transmission entity **145** may include one or more antenna panels. In some configurations, various functions of each access network entity **140** or base station **105** may be distributed across various network devices (e.g., radio heads and ANCs) or consolidated into a

single network device (e.g., a base station **105**).

(45) The wireless communications system **100** may operate using one or more frequency bands, typically in the range of 300 megahertz (MHz) to 300 gigahertz (GHz). Generally, the region from 300 MHz to 3 GHz is known as the ultra-high frequency (UHF) region or decimeter band because the wavelengths range from approximately one decimeter to one meter in length. The UHF waves may be blocked or redirected by buildings and environmental features, but the waves may penetrate structures sufficiently for a macro cell to provide service to the UEs **115** located indoors. The transmission of UHF waves may be associated with smaller antennas and shorter ranges (e.g., less than 100 kilometers) compared to transmission using the smaller frequencies and longer waves of the high frequency (HF) or very high frequency (VHF) portion of the spectrum below 300 MHz.

(46) The wireless communications system **100** may also operate in a super high frequency (SHF) region using frequency bands from 3 GHz to 30 GHz, also known as the centimeter band, or in an extremely high frequency (EHF) region of the spectrum (e.g., from 30 GHz to 300 GHz), also known as the millimeter band. In some examples, the wireless communications system **100** may support millimeter wave (mmW) communications between the UEs **115** and the base stations **105**, and EHF antennas of the respective devices may be smaller and more closely spaced than UHF antennas. In some examples, this may facilitate use of antenna arrays within a device. The propagation of EHF transmissions, however, may be subject to even greater atmospheric attenuation and shorter range than SHF or UHF transmissions. The techniques disclosed herein may be employed across transmissions that use one or more different frequency regions, and designated use of bands across these frequency regions may differ by country or regulating body.

(47) The wireless communications system **100** may utilize both licensed and unlicensed radio frequency spectrum bands. For example, the wireless communications system **100** may employ License Assisted Access (LAA), LTE-Unlicensed (LTE-U) radio access technology, or NR technology in an unlicensed band such as the 5 GHz industrial, scientific, and medical (ISM) band. When operating in unlicensed radio frequency spectrum bands, devices such as the base stations **105** and the UEs **115** may employ carrier sensing for collision detection and avoidance. In some examples, operations in unlicensed bands may be based on a carrier aggregation configuration in conjunction with component carriers operating in a licensed band (e.g., LAA). Operations in unlicensed spectrum may include downlink transmissions, uplink transmissions, P2P transmissions, or D2D transmissions, among other examples.

(48) A base station **105** or a UE **115** may be equipped with multiple antennas, which may be used to employ techniques such as transmit diversity, receive diversity, multiple-input multiple-output (MIMO) communications, or beamforming. The antennas of a base station **105** or a UE **115** may be located within one or more antenna arrays or antenna panels, which may support MIMO operations or transmit or receive beamforming. For example, one or more base station antennas or antenna arrays may be co-located at an antenna assembly, such as an antenna tower. In some examples, antennas or antenna arrays associated with a base station **105** may be located in diverse geographic locations. A base station **105** may have an antenna array with a number of rows and columns of antenna ports that the base station **105** may use to support beamforming of communications with a UE **115**. Likewise, a UE **115** may have one or more antenna arrays that may support various MIMO or beamforming operations. Additionally or alternatively, an antenna panel may support radio frequency beamforming for a signal transmitted via an antenna port.

(49) The base stations **105** or the UEs **115** may use MIMO communications to exploit multipath signal propagation and increase the spectral efficiency by transmitting or receiving multiple signals via different spatial layers. Such techniques may be referred to as spatial multiplexing. The multiple signals may, for example, be transmitted by the transmitting device via different antennas or different combinations of antennas. Likewise, the multiple signals may be received by the receiving device via different antennas or different combinations of antennas. Each of the multiple signals may be referred to as a separate spatial stream and may carry bits associated with the same

data stream (e.g., the same codeword) or different data streams (e.g., different codewords). Different spatial layers may be associated with different antenna ports used for channel measurement and reporting. MIMO techniques include single-user MIMO (SU-MIMO), where multiple spatial layers are transmitted to the same receiving device, and multiple-user MIMO (MU-MIMO), where multiple spatial layers are transmitted to multiple devices.

(50) Beamforming, which may also be referred to as spatial filtering, directional transmission, or directional reception, is a signal processing technique that may be used at a transmitting device or a receiving device (e.g., a base station **105**, a UE **115**) to shape or steer an antenna beam (e.g., a transmit beam, a receive beam) along a spatial path between the transmitting device and the receiving device. Beamforming may be achieved by combining the signals communicated via antenna elements of an antenna array such that some signals propagating at particular orientations with respect to an antenna array experience constructive interference while others experience destructive interference. The adjustment of signals communicated via the antenna elements may include a transmitting device or a receiving device applying amplitude offsets, phase offsets, or both to signals carried via the antenna elements associated with the device. The adjustments associated with each of the antenna elements may be defined by a beamforming weight set associated with a particular orientation (e.g., with respect to the antenna array of the transmitting device or receiving device, or with respect to some other orientation).

(51) A base station **105** or a UE **115** may use beam sweeping techniques as part of beam forming operations. For example, a base station **105** may use multiple antennas or antenna arrays (e.g., antenna panels) to conduct beamforming operations for directional communications with a UE **115**. Some signals (e.g., synchronization signals, reference signals, beam selection signals, or other control signals) may be transmitted by a base station **105** multiple times in different directions. For example, the base station **105** may transmit a signal according to different beamforming weight sets associated with different directions of transmission. Transmissions in different beam directions may be used to identify (e.g., by a transmitting device, such as a base station **105**, or by a receiving device, such as a UE **115**) a beam direction for later transmission or reception by the base station **105**.

(52) Some signals, such as data signals associated with a particular receiving device, may be transmitted by a base station **105** in a single beam direction (e.g., a direction associated with the receiving device, such as a UE **115**). In some examples, the beam direction associated with transmissions along a single beam direction may be determined based on a signal that was transmitted in one or more beam directions. For example, a UE **115** may receive one or more of the signals transmitted by the base station **105** in different directions and may report to the base station **105** an indication of the signal that the UE **115** received with a highest signal quality or an otherwise acceptable signal quality.

(53) In some examples, transmissions by a device (e.g., by a base station **105** or a UE **115**) may be performed using multiple beam directions, and the device may use a combination of digital precoding or radio frequency beamforming to generate a combined beam for transmission (e.g., from a base station **105** to a UE **115**). The UE **115** may report feedback that indicates precoding weights for one or more beam directions, and the feedback may correspond to a configured number of beams across a system bandwidth or one or more sub-bands. The base station **105** may transmit a reference signal (e.g., a cell-specific reference signal (CRS), a channel state information reference signal (CSI-RS)), which may be precoded or unprecoded. The UE **115** may provide feedback for beam selection, which may be a precoding matrix indicator (PMI) or codebook-based feedback (e.g., a multi-panel type codebook, a linear combination type codebook, a port selection type codebook). Although these techniques are described with reference to signals transmitted in one or more directions by a base station **105**, a UE **115** may employ similar techniques for transmitting signals multiple times in different directions (e.g., for identifying a beam direction for subsequent transmission or reception by the UE **115**) or for transmitting a signal in a single direction (e.g., for

transmitting data to a receiving device).

(54) A receiving device (e.g., a UE **115**) may try multiple receive configurations (e.g., directional listening) when receiving various signals from the base station **105**, such as synchronization signals, reference signals, beam selection signals, or other control signals. For example, a receiving device may try multiple receive directions by receiving via different antenna subarrays, by processing received signals according to different antenna subarrays, by receiving according to different receive beamforming weight sets (e.g., different directional listening weight sets) applied to signals received at multiple antenna elements of an antenna array, or by processing received signals according to different receive beamforming weight sets applied to signals received at multiple antenna elements of an antenna array, any of which may be referred to as “listening” according to different receive configurations or receive directions. In some examples, a receiving device may use a single receive configuration to receive along a single beam direction (e.g., when receiving a data signal). The single receive configuration may be aligned in a beam direction determined based on listening according to different receive configuration directions (e.g., a beam direction determined to have a highest signal strength, highest signal-to-noise ratio (SNR), or otherwise acceptable signal quality based on listening according to multiple beam directions).

(55) The wireless communications system **100** may be a packet-based network that operates according to a layered protocol stack. In the user plane, communications at the bearer or Packet Data Convergence Protocol (PDCP) layer may be IP-based. A Radio Link Control (RLC) layer may perform packet segmentation and reassembly to communicate over logical channels. A Medium Access Control (MAC) layer may perform priority handling and multiplexing of logical channels into transport channels. The MAC layer may also use error detection techniques, error correction techniques, or both to support retransmissions at the MAC layer to improve link efficiency. In the control plane, the Radio Resource Control (RRC) protocol layer may provide establishment, configuration, and maintenance of an RRC connection between a UE **115** and a base station **105** or a core network **130** supporting radio bearers for user plane data. At the physical layer, transport channels may be mapped to physical channels.

(56) The UEs **115** and the base stations **105** may support retransmissions of data to increase the likelihood that data is received successfully. HARQ feedback is one technique for increasing the likelihood that data is received correctly over a communication link **125**. HARQ may include a combination of error detection (e.g., using a cyclic redundancy check (CRC)), forward error correction (FEC), and retransmission (e.g., automatic repeat request (ARQ)). HARQ may improve throughput at the MAC layer in poor radio conditions (e.g., low signal-to-noise conditions). In some examples, a device may support same-slot HARQ feedback, where the device may provide HARQ feedback in a specific slot for data received in a previous symbol in the slot. In other cases, the device may provide HARQ feedback in a subsequent slot, or according to some other time interval.

(57) Wireless communications systems are widely deployed to provide various types of communication content such as voice, video, packet data, messaging, broadcast, and so on. These systems may be multiple-access systems capable of supporting communication with multiple users by sharing the available system resources (e.g., time, frequency, and power). A wireless network, for example a wireless local area network (WLAN), such as a Wi-Fi (i.e., Institute of Electrical and Electronics Engineers (IEEE) 802.11) network may include an access point (AP) that may communicate with one or more wireless or mobile devices. The AP may be coupled to a network, such as the Internet, and may enable a mobile device to communicate via the network (or communicate with other devices coupled to the access point). A wireless device may communicate with a network device bi-directionally. For example, in a WLAN, a device may communicate with an associated AP via downlink (e.g., the communication link from the AP to the device) and uplink (e.g., the communication link from the device to the AP). A wireless personal area network (PAN), which may include a Bluetooth connection, may provide for short range wireless connections

between two or more paired wireless devices. For example, wireless devices such as cellular phones may utilize wireless PAN communications to exchange information such as audio signals with wireless headsets.

(58) A UE **115** may receive two DCI in one PMO, each DCI scheduling the UE **115** for different PDSCH resources on a same component carrier. In some examples, a UE **115** may receive one DCI scheduling two PDSCHs in different component carriers. In some cases, the UE **115** may be scheduled according to both of these examples at the same time. For example, a UE **115** may receive at least two DCI in a PMO, where a first DCI schedules the UE **115** for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier, and a second DCI schedules the UE **115** for a third PDSCH resource on the first component carrier or the second component carrier. The techniques described herein support generating feedback for scheduling techniques where, during a PMO, a UE **115** is scheduled for PDSCH resources on multiple component carriers by a single DCI and, during the PMO, the UE **115** is scheduled for multiple PDSCH resources on a single component carrier.

(59) Additional techniques are described herein to support providing joint feedback for multiple PDSCH resources corresponding to different CORESET pool indices. The multiple PDSCH resources for the different CORESET pool indices may be scheduled for the same component carrier during the same PMO. The UE **115** may generate a HARQ ACK codebook for the PDSCH resources corresponding to the different CORESET pool indices and report the feedback on an uplink control channel. In some examples, the different CORESET pool indices may correspond to different TRPs.

(60) FIG. 2 illustrates an example of a wireless communications system **200** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. In some examples, wireless communications system **200** may implement aspects of wireless communication system **100**. Wireless communications system **200** may include base station **105-a** and UE **115-a**, which may be respective examples of a UE **115** and a base station **105** described with reference to FIG. 1.

(61) UE **115-a** may communicate with base station **105-a** on a set **205** of component carriers **210**. Base station **105-a** may transmit DCI **215** to schedule UE **115-a** for PDSCH resources **220** on one or more of the component carriers **210** for a data transmission to UE **115-a**. The DCI **215** may be transmitted to UE **115-a** during a PMO **230**, and UE **115-a** may monitor CORESETs in a PMO **230** to receive the DCI **215**. In some cases, base station **105-a** may transmit one or more DCI **215** on one or more component carriers **210** per-PMO **230** to schedule UE **115-a** for one or more PDSCH resources **220**. In some cases, UE **115-a** may be configured to report HARQ ACK feedback on a physical uplink control channel (PUCCH) resource **225** for multiple PDSCH resources **220**. In some cases, UE **115-a** may be configured to report HARQ ACK feedback for each scheduled PDSCH resource **220** in one HARQ ACK codebook on the PUCCH resource **225**. For example, UE **115-a** may generate a HARQ ACK codebook, where indices of the codebook correspond to ACK/NACK feedback for scheduled PDSCH resources **220**.

(62) The ordering of the codebook may be based on DAI values, which may be indicated by or correspond to DCI **215** which schedule the PDSCH resources **220**. A value of a counter DAI field in DCI formats may denote an accumulative number of serving cell and PMO pairs in which PDSCH reception or semi-persistent scheduled (SPS) PDSCH release associated with the DCI formats is present up to the current serving cell and current PMO. The DAI may increment first in an ascending order of serving cell index, then in ascending order of PMO index. In some cases, the serving cell may refer to a scheduled cell (e.g., a component carrier **210** on which the PDSCH resource **220** is scheduled) and not the scheduling cell (e.g., a component carrier **210** on which the DCI **215** is received).

(63) In an example, UE **115-a** may receive DCI **215-a** and DCI **215-b** in first PMO **230-a** and DCIS **215-c**, **215-d**, and **215-e** in second PMO **230-b**. Component carrier **210-a** and component

carrier **210-b** may be configured with self-scheduling, and component carrier **210-c** may be configured with cross-carrier scheduling (e.g., from component carrier **210-a**). Each DCI **215** may schedule a PDSCH resource **220**, and the value of a counter DAI may be indicated in each DCI **215**.

(64) As described, the DAI may be ordered first in ascending order of serving cell index, then in ascending order of PMO. DCI **215-a** and DCI **215-b** may occur in PMO **230-a**, which has an earlier PMO index than PMO **230-b**, so DCI **215-a** and DCI **215-b** may be ordered first and before DCIs **215-c**, **215-d**, and **215-e**. DCI **215-a** may schedule PDSCH resource **220-a** on component carrier **210-b**, and DCI **215-b** may schedule PDSCH resource **220-b** on component carrier **210-c**. Per the ascending ordering of component carriers, DCI **215-a** may correspond to, or indicate, a first DAI index, and DCI **215-b** may correspond to a second DAI index. For PMO **230-b**, DCI **215-c** may schedule PDSCH resource **220-c** on component carrier **210-a**, DCI **215-d** may schedule PDSCH resource **220-d** on component carrier **210-b**, and DCI **215-e** may schedule PDSCH resource **220-e** on component carrier **210-c**. According to the component carrier ordering, DCI **215-c** may correspond to a third DAI index, DCI **215-d** may correspond to a fourth DAI index, and DCI **215-e** may correspond to a fifth DAI index.

(65) UE **115-a** may construct the HARQ ACK codebook corresponding to the PDSCH resources **220** based on the counter DAI values. For example, a first index in the codebook may include HARQ ACK feedback for PDSCH resource **220-a**, the second index in the codebook may include HARQ ACK feedback for PDSCH resource **220-b**, and so on. In some cases, there may be a gap or a hole in the counter DAI values. For example, if UE **115-a** does not receive or misses DCI **215-c**, UE **115-a** may determine that UE **115-a** never received a DCI **215** corresponding to the third index, and UE **115-a** may include a NACK in the corresponding index in the codebook. In some cases, the HARQ ACK codebook may be an example of a Type 2 dynamic HARQ ACK codebook.

(66) UE **115-a**, and other UEs **115** described herein, may support multiple different techniques for PDSCH resource scheduling. In some examples, UE **115-a** may receive two DCI **215** in one PMO **230**, each DCI **215** scheduling UE **115-a** for different PDSCH resources **220** on a same component carrier **210**. In some cases, the DAI ordering in cases where multiple DCIs in the same PMO schedule the same serving cell may be based on PDSCH reception start time. For example, DAI may be ordered first based on an increasing order of PDSCH reception start time for the same serving cell scheduled during a same PMO, then in ascending order of serving cell index, then in ascending order of PMO index. As an example, Frequency Range 1 (FR1), with 30 kHz subcarrier spacing (SCS), may schedule Frequency Range 2 (FR2), with 120 kHz SCS, as one slot in FR1 may be equal to 4 slots in FR2, and the scheduling component carrier in FR1 may schedule multiple PDSCH resources **220** by multiple DCI **215** in the same PMO **230**. In some cases, UE **115-a** may indicate support for this scheduling by reporting a UE capability, such as “PDSCH-Number-perMOperCell.” In some cases, UE **115-a** may report a number of PDSCH supported per PMO per cell, N.sub.PDSCH.sup.MO.

(67) In some examples, UE **115-a** may receive one DCI **215** scheduling two PDSCH resources **220** in different component carriers **210**. A DCI **215** which schedules two PDSCH resources **220** may be referred to as a multi-component carrier scheduling DCI.

(68) In some cases, DAI ordering and numbering may be adjusted for a DCI **215** which schedules multiple PDSCH resources **220**. In a first example, counter DAI may be incremented by one value per DCI **215**, even when a DCI **215** schedules two component carriers **210**. However, UE **115-a** may generate two HARQ ACK bits per DAI position in the codebook. If a DCI **215** schedules just one PDSCH resource **220**, then the second bit in the codebook corresponding to the DCI **215** may be a NACK. In the first example, UE **115-a** may identify an associated component carrier index for a DCI **215** that schedules multiple (e.g., two) component carriers **210**, so that the DCI **215** is associated with one of the scheduled component carriers **210**. For example, UE **115-a** may identify either a larger component carrier index or a smaller component carrier index for the associated

component carrier index.

(69) For DAI ordering in this first example, a counter DAI in a current DCI may denote the accumulative number of DCI and PMO pairs in which PDSCH reception or SPS PDSCH release associated with a DCI format is present up to the current DCI and current PMO, first in ascending order of an associated serving cell index with DCIS in a given PMO, then in ascending order of PMO index. The HARQ ACK codebook may be generated based on the counter DAI definition and the counter DAI values of the received DCIS.

(70) In a second example of multi-component carrier scheduling DCI, a DCI **215** may indicate one DAI value per scheduled PDSCH resource **220**. For example, if a DCI **215** schedules two PDSCH resources **220**, the DCI may indicate two DAI values, one for each scheduled PDSCH resource **220**.

(71) In some cases, UE **115-a** may be scheduled according to both of these examples at the same time. For example, UE **115-a** may receive at least two DCI **215** in a PMO **230**, where a first DCI **215** schedules UE **115-a** for a first PDSCH resource **220** on a first component carrier **210** and a second PDSCH resource **220** on a second component carrier **210**, and a second DCI **215** schedules UE **115-a** for a third PDSCH resource **220** on the first component carrier **210** or the second component carrier **210**. The techniques described herein support generating feedback for cases where, during a PMO, a UE **115** is scheduled for PDSCH resources **220** on multiple component carriers **210** by a single DCI **215** and, during the PMO **230**, the UE **115** is scheduled for multiple PDSCH resources **220** on a single component carrier **210**.

(72) Other examples are provided, or these techniques can be applied for other examples. For example, the UE **115** may receive two multi-component carrier scheduling DCIS **215** in the same PMO **230** both scheduling the same component carriers **210**. In some cases, there may be two multi-component carrier scheduling DCIS in the same PMO, where a first DCI **215** is for a first and second component carrier and the second DCI **215** is for a first and a third component carrier. In some cases, there may be a first DCI **215** scheduling a single component carrier **210** and a second DCI **215** scheduling multiple component carriers **210** in the same PMO **230**, where the first DCI **215** schedules a first component carrier **210**, and the second DCI **215** schedules the first component carrier **210** and a second component carrier **210**. A UE **115** described herein may be able to provide HARQ ACK feedback (e.g., in a HARQ ACK codebook) for any of these scheduling examples, among others.

(73) Additional techniques are described herein to support providing joint feedback for multiple PDSCH resources **220** corresponding to different CORESET pool indices. The multiple PDSCH resources **220** for the different CORESET pool indices may be scheduled for the same component carrier **210** during the same PMO **230**. The UE may generate a HARQ ACK codebook for the PDSCH resources **220** corresponding to the different CORESET pool indices and report the feedback on a PUCCH resource **225**. In some examples, the different CORESET pool indices may correspond to different TRPs.

(74) FIG. 3 illustrates an example of a scheduling scheme **300** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. In some examples, scheduling scheme **300** may implement aspects of wireless communication system **100**.

(75) A base station **105** may transmit DCI **315** to schedule a UE **115** for PDSCHs **320** on one or more component carriers **305**. The UE **115** may generate feedback for the PDSCH **320** and transmit the feedback on a PUCCH **325**. The UE **115** may generate a HARQ ACK codebook, where each index of the codebook corresponds to a DCI which schedules a PDSCH resource.

(76) The UE **115** may receive two DCI **315** scheduling component carrier **305-c**, and one of the DCI **315** may schedule multiple component carriers **305**. For example, the UE **115** may receive DCI **315-a**, DCI **315-b**, and DCI **315-b** during a PMO **310**. DCI **315-a** may schedule PDSCH **320-a**, DCI **315-b** may schedule PDSCH **320-b** and PDSCH **320-c**, and DCI **315-c** may schedule

PDSCH 320-d.

(77) In the example of the scheduling scheme 300, a counter DAI may be incremented by one value per DCI 315, even when a DCI 315 schedules two component carriers 305. The UE 115 may generate two bits per DAI position in the codebook. If a DCI 315 schedules just one PDSCH 320, then the second bit for the DCI 315 may be a NACK.

(78) The UE 115 may identify an associated component carrier index for each DCI 315. If a DCI 315 schedules one component carrier 305, the associated component carrier index may be the scheduled component carrier index. If a DCI 315 schedules two component carriers, the associated component carrier index may be one of the scheduled component carrier indices. In some cases, the associated component carrier index may correspond to a scheduled component carrier with a higher index or a lower index.

(79) DCI 315-a may schedule PDSCH 320-a in component carrier 305-b, so the associated component carrier index may be “2” for DCI 315-a. DCI 315-b may schedule PDSCH 320-b and PDSCH 320-c, which may be in component carrier 305-a and component carrier 305-c, respectively. In the example of the scheduling scheme 300, the UE 115 may identify component carrier 305-c for the associated component carrier index, so the associated component carrier index may be “3” for DCI 315-b. DCI 315-c may schedule PDSCH 320-d on component carrier 305-c, so the associated component carrier index may also be “3” for DCI 315-c.

(80) If two or more DCIs 315 have the same associated component carrier index in the same PMO, the value of a DAI may be ordered in increasing order of the PDSCH reception starting time in the associated component carrier index. For example, PDSCH 320-b is received before PDSCH 320-d, so PDSCH 320-b may have the lower DAI value. DCI 315-a may have the lower associated component carrier index of “2”, so DCI 315-a may be associated with a first DAI. DCI 315-b and DCI 315-c may each have the associated component carrier index of “3”, but PDSCH 320-b may be received before PDSCH 320-d, so DCI 315-b may have a second DAI, and DCI 315-c may be associated with a third DAI.

(81) The UE 115 may generate a HARQ ACK codebook based on the DAI and transmit the codebook on a PUCCH 325. A first index 330-a of the codebook may include two bits of HARQ ACK feedback for PDSCH 320-a, a second index 330-b of the codebook may include two bits of HARQ ACK feedback for PDSCH 320-b and PDSCH 320-c, and a third index 330-c of the codebook may include two bits of HARQ ACK feedback for PDSCH 320-d. The second bit of HARQ ACK feedback for PDSCH 320-a and PDSCH 320-d may be NACKs, as the scheduling DCIs 315 schedule just one PDSCH 320 each.

(82) FIG. 4 illustrates an example of a scheduling scheme 400 that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. In some examples, scheduling scheme 400 may implement aspects of wireless communication system 100.

(83) A base station 105 may transmit DCI 415 to schedule a UE 115 for PDSCHs 420 on one or more component carriers 405. The UE 115 may generate feedback for the PDSCH 420 and transmit the feedback on a PUCCH 425. The UE 115 may generate a HARQ ACK codebook, where each index of the codebook corresponds to a DCI which schedules a PDSCH resource.

(84) The UE 115 may receive two DCI 415 scheduling component carrier 405-c, and one of the DCI 415 may schedule multiple component carriers 405. For example, the UE 115 may receive DCI 415-a, DCI 415-b, and DCI 415-b during a PMO 410. DCI 415-a may schedule PDSCH 420-a, DCI 415-b may schedule PDSCH 420-b and PDSCH 420-c, and DCI 415-c may schedule PDSCH 420-d.

(85) In the example of the scheduling scheme 400, a counter DAI may be incremented by one value per DCI 415, even when a DCI 415 schedules two component carriers 405. The UE 115 may generate two bits per DAI position in the codebook. If a DCI 415 schedules two PDSCH 420, then each bit of the two bits may correspond to feedback for one of the two PDSCH 420. If a DCI 415

schedules just one PDSCH **420**, then the second bit for the DCI **415** may be a NACK.

(86) The UE **115** may identify an associated component carrier index for each DCI **415**. If a DCI **415** schedules one component carrier **405**, the associated component carrier index may be the scheduled component carrier index. If a DCI **415** schedules two component carriers, the associated component carrier index may be one of the scheduled component carrier indices. In some cases, the associated component carrier index may correspond to a scheduled component carrier with a higher index or a lower index.

(87) DCI **415-a** may schedule PDSCH **420-a** in component carrier **405-b**, so the associated component carrier index may be “2” for DCI **415-a**. DCI **415-b** may schedule PDSCH **420-b** and PDSCH **420-c**, which may be in component carrier **405-a** and component carrier **405-c**, respectively. In the example of the scheduling scheme **400**, the UE **115** may identify component carrier **405-a** for the associated component carrier index, so the associated component carrier index may be “1” for DCI **415-b**. DCI **415-c** may schedule PDSCH **420-d** on component carrier **405-c**, so the associated component carrier index may also be “3” for DCI **415-c**. Each DCI **415** may have a different associated component carrier index, so the DAI ordering may be based on the associated component carrier indices. For example, DCI **415-b** may have a first DAI, DCI **415-a** may have a second DAI, and DCI **415-c** may have a third DAI.

(88) The UE **115** may generate a HARQ ACK codebook based on the DAI and transmit the codebook on a PUCCH **425**. A first index **430-a** of the codebook may include two bits of HARQ ACK feedback for PDSCH **420-b** and PDSCH **420-c**, a second index **430-b** of the codebook may include two bits of HARQ ACK feedback for PDSCH **420-a**, and a third index **430-c** of the codebook may include two bits of HARQ ACK feedback for PDSCH **420-d**. The second bit of HARQ ACK feedback for PDSCH **420-a** and PDSCH **420-d** may be NACKs, as the scheduling DCIS **415** schedule just one PDSCH **420** each.

(89) FIG. 5 illustrates an example of a scheduling scheme **500** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. In some examples, scheduling scheme **500** may implement aspects of wireless communication system **100**.

(90) A base station **105** may transmit DCI **515** to schedule a UE **115** for PDSCHs **520** on one or more component carriers **505**. The UE **115** may generate feedback for the PDSCH **520** and transmit the feedback on a PUCCH **525**. The UE **115** may generate a HARQ ACK codebook, where each index of the codebook corresponds to a DCI which schedules a PDSCH resource.

(91) The UE **115** may receive two DCI **515** scheduling component carrier **505-a**, and one of the DCI **515** may schedule multiple component carriers **505**. Additionally, the UE **115** may receive two DCI **515** scheduling component carrier **505-a**, and one of the DCI **515** may schedule multiple component carriers **505**. For example, the UE **115** may receive DCI **515-a**, DCI **515-b**, DCI **515-c**, and DCI **515-d** during a PMO **510**. DCI **515-a** may schedule PDSCH **520-a** and PDSCH **520-d**, DCI **515-b** may schedule PDSCH **520-b**, DCI **515-c** may schedule PDSCH **520-c**, and DCI **515-d** may schedule PDSCH **520-e**.

(92) In the example of the scheduling scheme **500**, a DCI **515** that schedules two PDSCH **520** in two component carriers **505** may indicate two DAI values corresponding to the two scheduled component carriers **505**. For example, DCI **515-a** may schedule PDSCH **520-a** and PDSCH **520-d**, and DCI **515-a** may therefore indicate two DAI values.

(93) If another DCI schedules at least one of the two component carriers **505** which is scheduled by a multi-component carrier scheduling DCI, the value of the DAI may be based on which PDSCH has an earlier starting time. For example, DCI **515-a** and DCI **515-b** both schedule component carrier **505-a**, but PDSCH **520-a** may be earlier than PDSCH **520-b**. Therefore, one of the two DAI corresponding to DCI **515-a**, which schedules PDSCH **520-a**, may be ordered first (e.g., before) the DAI corresponding to DCI **515-b**, which schedules PDSCH **520-b**. Similarly, DCI **515-a** and DCI **515-d** both schedule component carrier **505-c**, but PDSCH **520-d** occurs before PDSCH **520-e** in

the time domain. Therefore, the other one of the two DAI for DCI 515-*a* may be ordered before the DAI corresponding to DCI 515-*d*.

(94) A first index 530-*a* of the codebook may correspond to DCI 515-*a*, which schedules PDSCH 520-*a* on component carrier 505-*a*. A second index 530-*b* may correspond to DCI 515-*b*, which also schedules on component carrier 505-*a*, but PDSCH 520-*b* occurs after PDSCH 520-*a* in the time domain. The next highest serving cell index, corresponding to component carrier 505-*b*, includes PDSCH 520-*c*, which is scheduled by DCI 515-*c*. Therefore, a third index 530-*c* may correspond to DCI 515-*c*. Component carrier 505-*c* includes PDSCH 520-*d* and PDSCH 520-*e*. A fourth index 530-*d* may correspond to DCI 515-*a*, as PDSCH 520-*d* occurs before PDSCH 520-*e* in the time domain. A fifth index 530-*e* may correspond to DCI 515-*d*. Each index 530 may include HARQ ACK feedback for PDSCH 520 scheduled by the corresponding DCI 515. For example, first index 530-*a* may include HARQ ACK feedback for PDSCH 520-*a*.

(95) FIG. 6 illustrates an example of a joint feedback scheme 600 that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. In some examples, joint feedback scheme 600 may implement aspects of wireless communication system 100.

(96) In some cases, a UE 115 may support joint feedback for transmissions from multiple TRPs. In some cases, different TRPs may have different CORESET pool index values. For example, a CORESET pool index may be configured per CORESET, and the UE 115 may group the CORESETs into two groups corresponding to a CORESET pool index values 0 and 1. For joint feedback, DAI may first be ordered in increasing order of CORESET pool index values in the same component carrier and same PMO 610, second in increasing order of component carrier index, and third in increasing order of PMO index. For example, if the UE 115 is not provided a CORESET pool index for an active downlink bandwidth part of a serving cell or is provided CORESET pool index with value 0 for one or more first CORESETs, and the UE 115 is provided CORESET pool index with value 1 for one or more second CORESETs, and the UE 115 is configured for joint feedback, the value of the counter DAI may be in the order of the first CORESETs and then the second CORESETs for a same serving cell index and a same PMO 610.

(97) For HARQ ACK codebook construction based on DAI values, each component carrier with two values of CORESET pool index may be counted two times. A PDSCH 620 may be associated with a CORESET pool index value through the scheduling DCI 615. For example, the PDSCH 620 may be associated with CORESET pool index value 0 if the scheduling DCI 615 is received in a first CORESET, or the PDSCH 620 may be associated with CORESET pool index value 1 if the scheduling DCI 615 is received in a second CORESET. For example, if the UE 115 is not provided a CORESET pool index for an active downlink bandwidth part of a serving cell or is provided CORESET pool index with value 0 for one or more first CORESETs, and the UE 115 is provided CORESET pool index with value 1 for one or more second CORESETs, and the UE 115 is configured for joint feedback, the serving cell may be counted two times, where the first time corresponds to the first group of CORESETs and the second time corresponds to the second group of CORESETs.

(98) In some cases, the UE 115 may indicate support for being scheduled with multiple PDSCH per PMO per cell. For example, the UE 115 may send a UE capability to a base station 105 indicating support for being scheduled for multiple PDSCH on a component carrier during a single PMO. In some cases, the UE 115 may indicate support for “PDSCH-Number-perMOperCell” to the base station 105. In some cases, the UE 115 may indicate a number of PDSCHs 620 the UE 115 can be scheduled with per component carrier 605 per PMO 610, or N.sub.PDSCH.sup.MO.

(99) In the example of joint feedback scheme 600, the UE 115 may not be provided a CORESET pool index for an active downlink BWP of a serving cell, or the UE 115 may be provided CORESET pool index with value 0 for one or more first CORESETs. Additionally, the UE 115 may be provided CORESET pool index with value 1 for one or more second CORESETs. The UE 115

may receive, during a PMO **610**, DCI **615-a** through DCI **615-d** on component carrier **605-a** and receive DCI **615-e** and DCI **615-f** on component carrier **605-b**. DCI **615-a**, DCI **615-b**, DCI **615-e**, and DCI **615-f** may be associated with a control resource pool index with value 0, and DCI **615-c** and DCI **615-d** may be associated with a CORESET pool index with value 1.

(100) There may be a total number of DCIs **615** scheduling the same component carrier **605**, such as the component carrier **605** with both values of the CORESET pool index, in the same PMO **610**. In a first example, there may be up to twice as many DCIs as indicated by the UE capability. For example, the UE **115** may indicate support for “PDSCH-Number-perMOperCell,” which may indicate the UE capability to enable ordering the DAIs with respect to PDSCH start time for the same component carrier and same PMO. Additionally, or alternatively, the UE **115** may indicate a number of PDSCHs that can be scheduled at the same PMO for the same component carrier, which may be denoted by $N_{\text{sub.PDSCH.sup.MO}}$. In a first example, there may be up to $2 \cdot N_{\text{sub.PDSCH.sup.MO}}$ DCIs scheduling the same component carrier **605** in the same PMO **610** for the component carrier **605** with both CORESET pool index values. For example, the number $N_{\text{sub.PDSCH.sup.MO}}$ indicated through UE capability signaling may correspond to the number PDSCHs associated with a given value of CORESET pool index that can be scheduled per component carrier during the same PMO.

(101) In an example, $N_{\text{sub.PDSCH.sup.MO}}$ may be 2. Therefore, there may be up to 4 DCIs **615** scheduling the same component carrier **605** in the same PMO **610**. In an example illustrated by the joint feedback scheme **600**, DCI **615-a** through DCI **615-d** (e.g., 4 DCIs **615**) may be received during PMO **610** and schedule PDSCH **620-a** through PDSCH **620-d**, respectively, in component carrier **605-a**. DCI **615-a** and DCI **615-b** may be associated with CORESET pool index 0, and DCI **615-c** and DCI **615-d** may be associated with CORESET pool index 1, so component carrier **605-a** may have both values of CORESET pool indices.

(102) In some cases, DAI may be ordered based on a total number of DCI scheduling the same component carrier **605** in the same PMO **610**. For example, DAI may be ordered first in increasing order of PDSCH start time for the same CORESET pool index, same component carrier **605**, and same PMO **610**, then DAI may be ordered in increasing order of CORESET pool index value for the same component carrier **605** and same PMO **610**, then DAI may be ordered in increasing order of component carrier index for the same PMO **610**, then DAI may be ordered in increasing order of PMO index. Component carrier **605-a**, with both values of CORESET pool indices, may be counted $2 \cdot N_{\text{sub.PDSCH.sup.MO}}$ times for creating the HARQ ACK codebook in a given PMO.

(103) For example, for CORESET pool index 0 in component carrier **605-a**, PDSCH **620-a** may occur earlier than PDSCH **620-b**, so DCI **615-a** may be associated with a first DAI **630-a** and DCI **615-b** may be associated with a second DAI **630-b**. After the DAI for CORESET pool index 0 in component carrier **605-a** for PMO **610** have been ordered, the DAI for CORESET pool index 1 in component carrier **605-a** for PMO **610** may be ordered. In component carrier **605-a**, PDSCH **620-c** may occur before PDSCH **620-d**, so DCI **615-c** may be associated with a third DAI **630-c** and DCI **615-d** may be associated with a fourth DAI **630-d**. After the DAI in component carrier **605-a** have been ordered, DAI in component carrier **605-b** may be ordered. PDSCH **620-e** and PDSCH **620-f** may both be associated with CORESET pool index 0, but PDSCH **620-e** may occur before PDSCH **620-f** in the time domain. Therefore, DCI **615-e** may be associated with a fifth DAI **630-e**, and DCI **615-f** may be associated with a sixth DAI **630-f**. The UE **115** may generate the HARQ ACK codebook by setting bits in the codebook with HARQ ACK feedback for PDSCH **620** scheduled by the associated DCI **615** and transmit the HARQ ACK codebook on PUCCH **625**.

(104) FIG. 7 illustrates an example of a joint feedback scheme **700** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. In some examples, joint feedback scheme **700** may implement aspects of wireless communication system **100**.

(105) As described with reference to FIG. 6, a UE **115** may be configured for joint feedback

reporting for multiple CORESET pools. The UE 115 may indicate support for being scheduled with multiple PDSCH per PMO per cell. For example, the UE 115 may send a UE capability to a base station 105 indicating support for being scheduled for multiple PDSCH on a component carrier during a single PMO. In some cases, the UE 115 may indicate support for ordering the DAIs with respect to PDSCH start time for the same component carrier and same PMO to the base station 105 (e.g., by indicating a UE capability). In some cases, the UE 115 may indicate a number of PDSCHs 720 the UE 115 can be scheduled with per component carrier 705 per PMO 710. In other words, the number $N_{\text{sub.PDSCH.sup.MO}}$ indicated through UE capability signaling is interpreted as the total number PDSCHs associated with both values of CORESET pool index that can be scheduled per component during the same PMO, and not per CORESET index value.

(106) In the example of joint feedback scheme 700, the UE 115 may not be provided a CORESET pool index for an active downlink bandwidth part of a serving cell, or the UE 115 may be provided CORESET pool index with value 0 for one or more first CORESETs. Additionally, the UE 115 may be provided a CORESET pool index with value 1 for one or more second CORESETs. The UE 115 may receive, during a PMO 710, DCI 715-a through DCI 715-d on a component carrier 705. DCI 715-a and DCI 715-c may be associated with a control resource pool index with value 0, and DCI 715-b, and DCI 715-d may be associated with a CORESET pool index with value 1.

(107) There may be a total number of DCIs 715 scheduling the same component carrier 705, such as the component carrier 705 with both values of the CORESET pool index, in the same PMO 710. A first example may be described with reference to FIG. 6. In a second example, there may be up to as many DCIs as indicated by the UE. For example, the UE 115 may indicate support for “PDSCH-Number-perMOperCell,” and there may be up to $N_{\text{sub.PDSCH.sup.MO}}$ DCIs scheduling the same component carrier 705 in the same PMO 710 for the component carrier 705 with both CORESET pool index values. In this example, two PDSCHs 720 associated with different CORESET pool index values may have a same starting point.

(108) In an example, $N_{\text{sub.PDSCH.sup.MO}}$ may be 4. Therefore, there may be up to 4 DCIs 715 scheduling the same component carrier 705 in the same PMO 710. In an example illustrated by the joint feedback scheme 700, DCI 715-a through DCI 715-d (e.g., 4 DCIs 715) may be received during PMO 710 and schedule PDSCH 720-a through PDSCH 720-d, respectively, in component carrier 705. DCI 715-a and DCI 715-c may be associated with CORESET pool index 0, and DCI 715-b and DCI 715-d may be associated with CORESET pool index 1, so component carrier 705 may have both values of CORESET pool indices.

(109) In some cases, DAI may be ordered based on a total number of DCI scheduling the same component carrier 705 in the same PMO 710. For example, DAI may be ordered first in increasing order of CORESET pool index value for the same PDSCH start time, the same component carrier 705, and same PMO 710, then DAI may be ordered in increasing order of PDSCH starting time for the same component carrier 705 and same PMO 710, then DAI may be ordered in increasing order of component carrier index for the same PMO 710, then DAI may be ordered in increasing order of PMO index. Component carrier 705, with both values of CORESET pool indices, may be counted $N_{\text{sub.PDSCH.sup.MO}}$ times for creating the HARQ ACK codebook in a given PMO 710.

(110) For example, PDSCH 720-a and PDSCH 720-b may have a same start time and be scheduled on the same component carrier 705 during the same PMO 710, but PDSCH 720-a may be associated with the smaller CORESET pool index value. Therefore, DCI 715-a may be associated with a first DAI 730-a, and DCI 715-b may be associated with a second DAI 730-b. PDSCH 720-c may have the next earliest PDSCH start time, so DCI 715-c may be associated with a third DAI 730-c and DCI 715-d may be associated with a fourth DAI 730-d. The UE 115 may generate the HARQ ACK codebook by setting bits in the codebook with HARQ ACK feedback for PDSCH 720 scheduled by the associated DCI 715 and transmit the HARQ ACK codebook on PUCCH 725.

(111) FIG. 8 illustrates an example of a process flow 800 that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of

the present disclosure. In some examples, the process flow **800** may implement aspects of wireless communication system **100**. The process flow **800** may be implemented by UE **115-b**, base station **105-b**, or both, which may be examples of a UE **115** and a base station **105** described with reference to FIGS. **1** and **2**.

(112) At **805**, UE **115-b** may receive, from base station **105-b** during a PMO, first DCI scheduling UE **115-b** for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier. At **810**, UE **115-b** may receive, from base station **105-b** during the PMO, second DCI scheduling UE **115-b** for a third PDSCH resource on the second component carrier. UE **115-b** may monitor for data from base station **105-b** during the first, second, and third PDSCH resources.

(113) At **815**, UE **115-b** may identify a set of DAIS for the first DCI and the second DCI, where the first DCI has one or more DAIS whose values are based on the first DCI scheduling PDSCH resources on different component carriers.

(114) In some cases, UE **115-b** may generate a HARQ ACK codebook whose order is based on the set of DAIs. At **820**, UE **115-b** may transmit feedback (e.g., including the codebook) based on the set of DAIs.

(115) FIG. **9** illustrates an example of a process flow **900** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. In some examples, process flow **900** may implement aspects of wireless communication system **100**. The process flow **900** may be implemented by UE **115-c**, TRP **105-c**, TRP **105-d**, or any combination thereof. UE **115-c** may be an example of a UE **115** described with reference to FIGS. **1** and **2**. In some cases, TRP **105-c** and TRP **105-d** may each be an example of a base station **105** described with reference to FIGS. **1** and **2**, or TRP **105-c** and TRP **105-d** may be examples of TRPs of a base station **105**. For example, TRP **105-c** and TRP **105-d** may separate transmitters and receivers, which may convey communications for a base station **105**.

(116) At **905**, UE **115-c** may receive, during a PMO, one or more first DCI scheduling UE **115-c** for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index. At **910**, UE **115-c** may receive, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index. In some cases, the first CORESET pool index may be associated with TRP **105-c**, and the second CORESET pool index may be associated with TRP **105-d**.

(117) At **915**, UE **115-c** may identifying a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both schedule PDSCH resources on a same component carrier.

(118) UE **115-c** may transmit feedback based on the set of DAIs. For example, UE **115-c** may generate a HARQ ACK codebook including feedback for the set of PDSCH resources. In some cases, at **920**, UE **115-c** may transmit the feedback to TRP **105-c**. Additionally, or alternatively, UE **115-c** may transmit the feedback to TRP **105-d**.

(119) FIG. **10** shows a block diagram **1000** of a device **1005** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The device **1005** may be an example of aspects of a UE **115** as described herein. The device **1005** may include a receiver **1010**, a communication manager **1015**, and a transmitter **1020**. The device **1005** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(120) The receiver **1010** may receive information such as packets, user data, or control information associated with various information channels (e.g., control channels, data channels, and information related to feedback schemes for multiple component carrier scheduling and joint feedback reporting, etc.). Information may be passed on to other components of the device **1005**. The receiver **1010** may be an example of aspects of the transceiver **1315** described with reference

to FIG. 13. The receiver **1010** may utilize a single antenna or a set of antennas.

(121) The communication manager **1015** may receive, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier, identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, transmit feedback based on the set of DAIs, and receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier. The communication manager **1015** may also receive, from a base station during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, transmit feedback based on the set of DAIs, and receive, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index. The communication manager **1015** may be an example of aspects of the communication manager **1310** described herein.

(122) The communication manager **1015**, or its sub-components, may be implemented in hardware, code (e.g., software or firmware) executed by a processor, or any combination thereof. If implemented in code executed by a processor, the functions of the communication manager **1015**, or its sub-components may be executed by a general-purpose processor, a digital signal processor (DSP), an application-specific integrated circuit (ASIC), a field-programmable gate array (FPGA) or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described in the present disclosure.

(123) The communication manager **1015**, or its sub-components, may be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations by one or more physical components. In some examples, the communication manager **1015**, or its sub-components, may be a separate and distinct component in accordance with various aspects of the present disclosure. In some examples, the communication manager **1015**, or its sub-components, may be combined with one or more other hardware components, including but not limited to an input/output (I/O) component, a transceiver, a network server, another computing device, one or more other components described in the present disclosure, or a combination thereof in accordance with various aspects of the present disclosure.

(124) By including or configuring the communication manager **1015** in accordance with examples described herein, the device **1005** (e.g., a processor controlling or otherwise coupled to the receiver **1010**, the transmitter **1020**, the communication manager **1015**, or a combination thereof) may support techniques for reduced processing and reduced power consumption based on transmitting joint feedback for multiple DCI.

(125) The transmitter **1020** may transmit signals generated by other components of the device **1005**. In some examples, the transmitter **1020** may be collocated with a receiver **1010** in a transceiver module. For example, the transmitter **1020** may be an example of aspects of the transceiver **1315** described with reference to FIG. 13. The transmitter **1020** may utilize a single antenna or a set of antennas.

(126) FIG. 11 shows a block diagram **1100** of a device **1105** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The device **1105** may be an example of aspects of a device **1005**, or a UE **115** as described herein. The device **1105** may include a receiver **1110**, a communication manager **1115**, and a transmitter **1145**. The device **1105** may also include a processor. Each of these

components may be in communication with one another (e.g., via one or more buses).

(127) The receiver **1110** may receive information such as packets, user data, or control information associated with various information channels (e.g., control channels, data channels, and information related to feedback schemes for multiple component carrier scheduling and joint feedback reporting, etc.). Information may be passed on to other components of the device **1105**. The receiver **1110** may be an example of aspects of the transceiver **1315** described with reference to FIG. **13**. The receiver **1110** may utilize a single antenna or a set of antennas.

(128) The communication manager **1115** may be an example of aspects of the communication manager **1015** as described herein. The communication manager **1115** may include a multi-CC scheduling component **1120**, a DAI identifying component **1125**, a feedback component **1130**, and a PDSCH scheduling component **1140**. The communication manager **1115** may be an example of aspects of the communication manager **1310** described herein.

(129) The multi-CC scheduling component **1120** may receive, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier. The multi-CC scheduling component **1120** may receive, from a base station during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index.

(130) The DAI identifying component **1125** may identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers. The DAI identifying component **1125** may identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier.

(131) The PDSCH scheduling component **1140** may receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier. The PDSCH scheduling component **1140** may receive, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index.

(132) The feedback component **1130** may transmit feedback based on the set of DAIs.

(133) The transmitter **1145** may transmit signals generated by other components of the device **1105**. In some examples, the transmitter **1145** may be collocated with a receiver **1110** in a transceiver module. For example, the transmitter **1145** may be an example of aspects of the transceiver **1315** described with reference to FIG. **13**. The transmitter **1145** may utilize a single antenna or a set of antennas.

(134) FIG. **12** shows a block diagram **1200** of a communication manager **1205** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The communication manager **1205** may be an example of aspects of a communication manager **1015**, a communication manager **1115**, or a communication manager **1310** described herein. The communication manager **1205** may include a multi-CC scheduling component **1210**, a DAI identifying component **1215**, a feedback component **1220**, a codebook generating component **1225**, an ACK bits component **1230**, a PDSCH scheduling component **1240**, and a UE capability component **1245**. Each of these modules may communicate, directly or indirectly, with one another (e.g., via one or more buses).

(135) The multi-CC scheduling component **1210** may receive, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier.

(136) In some examples, the multi-CC scheduling component **1210** may receive, from a base station during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a

first CORESET pool index.

(137) The DAI identifying component **1215** may identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers. In some examples, the DAI identifying component **1215** may identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier. In some examples, the DAI identifying component **1215** may determine a first associated component carrier index for the first DCI based on a highest component carrier index of the first component carrier and the second component carrier. In some examples, the DAI identifying component **1215** may determine a first associated component carrier index for the first DCI based on a lowest component carrier index of the first component carrier and the second component carrier. In some examples, the DAI identifying component **1215** may determine that a first associated component carrier index for the first DCI and a second associated component carrier index for the second DCI are a same associated component carrier index based on the second PDSCH resource and the third PDSCH resource being scheduled on the second component carrier.

(138) In some examples, the DAI identifying component **1215** may determine a first DAI for the first DCI and a second DAI for the second DCI based on a time domain order of the second PDSCH resource and the third PDSCH resource. In some examples, the DAI identifying component **1215** may determine a first DAI for the first DCI corresponds to a first component carrier index associated with the first component carrier based on the first PDSCH resource. In some examples, the DAI identifying component **1215** may determine a second DAI for the second DCI corresponds to a second component carrier index associated with the second component carrier based on the third PDSCH resource. In some examples, the DAI identifying component **1215** may determine a first DAI for the first DCI associated with the first component carrier and the first PDSCH resource. In some examples, the DAI identifying component **1215** may determine a second DAI for the first DCI associated with the second component carrier and the second PDSCH resource.

(139) In some examples, the DAI identifying component **1215** may determine a third DAI for the second DCI associated with the second component carrier and the third PDSCH resource. In some examples, the DAI identifying component **1215** may receive, during the PMO, a third DCI scheduling the UE for a fourth PDSCH resource on the first component carrier. In some examples, the DAI identifying component **1215** may determine a fourth DAI for the third DCI associated with the first component carrier and the fourth PDSCH resource, where the fourth DAI and the first DAI are based on a temporal ordering of the first PDSCH resource and the fourth PDSCH resource. In some examples, the DAI identifying component **1215** may determine an ordering for the set of DAIs based on a temporal ordering of the PDSCH resources associated with a same CORESET pool index on the same component carrier scheduled during the PMO, then based on a CORESET pool index ordering on the same component carrier scheduled during the PMO, then based on a component carrier index ordering for the PMO, then based on a PMO ordering. In some examples, the DAI identifying component **1215** may determine an ordering for the set of DAIs based on a CORESET pool index ordering for the PDSCH resources having a common starting resource in a time domain on the same common component carrier scheduled during the PMO, then based on a temporal ordering of the PDSCH resources on the same component carrier scheduled during the PMO, then based on a component carrier index ordering for component carriers scheduled during the PMO, then based on a PMO index ordering.

(140) The feedback component **1220** may transmit feedback based on the set of DAIs.

(141) The PDSCH scheduling component **1240** may receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier. In some examples, the PDSCH scheduling component **1240** may receive, during the PMO, one or more

second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index. In some examples, the PDSCH scheduling component **1240** may determine the one or more first DCI allocate one or more third PDSCH resources in a second component carrier.

(142) The codebook generating component **1225** may generate a HARQ ACK codebook whose order is based on the set of DAIs.

(143) The ACK bits component **1230** may determine a set of ACK or NACK bits for each DAI of the set of DAIs. In some examples, the ACK bits component **1230** may determine feedback values for the set of ACK or NACK bits of a first DAI associated with the first DCI based on the first DCI scheduling a set of PDSCH resources, each of the set of ACK or NACK bits of the first DAI corresponding to a different one of the first PDSCH resource and the second PDSCH resource. In some examples, the ACK bits component **1230** may determine a first feedback value for a first bit of the set of ACK or NACK bits of a second DAI associated with the second DCI based on the second DCI scheduling a single PDSCH resource. In some examples, the ACK bits component **1230** may include a NACK for a second bit of the set of ACK or NACK bits of the second DAI associated with the second DCI.

(144) The UE capability component **1245** may transmit, to a base station, a UE capability associated with a number of PDSCH resources per PMO per cell, the number of PDSCH resources per PMO per cell, or both.

(145) FIG. **13** shows a diagram of a system **1300** including a device **1305** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The device **1305** may be an example of or include the components of device **1005**, device **1105**, or a UE **115** as described herein. The device **1305** may include components for bi-directional voice and data communications including components for transmitting and receiving communications, including a communication manager **1310**, a transceiver **1315**, an antenna **1320**, memory **1325**, and a processor **1335**. These components may be in electronic communication via one or more buses (e.g., bus **1340**).

(146) The communication manager **1310** may receive, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier, identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, transmit feedback based on the set of DAIs, and receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier. The communication manager **1310** may also receive, from a base station during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, transmit feedback based on the set of DAIs, and receive, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index.

(147) The transceiver **1315** may communicate bi-directionally, via one or more antennas, wired, or wireless links as described above. For example, the transceiver **1315** may represent a wireless transceiver and may communicate bi-directionally with another wireless transceiver. The transceiver **1315** may also include a modem to modulate the packets and provide the modulated packets to the antennas for transmission, and to demodulate packets received from the antennas.

(148) In some cases, the wireless device may include a single antenna **1320**. However, in some cases the device may have more than one antenna **1320**, which may be capable of concurrently transmitting or receiving multiple wireless transmissions.

(149) The memory **1325** may include random-access memory (RAM) and read-only memory (ROM). The memory **1325** may store computer-readable, computer-executable code **1330** including instructions that, when executed, cause the processor to perform various functions described herein. In some cases, the memory **1325** may contain, among other things, a basic I/O system (BIOS) which may control basic hardware or software operation such as the interaction with peripheral components or devices.

(150) The code **1330** may include instructions to implement aspects of the present disclosure, including instructions to support wireless communications. The code **1330** may be stored in a non-transitory computer-readable medium such as system memory or other type of memory. In some cases, the code **1330** may not be directly executable by the processor **1335** but may cause a computer (e.g., when compiled and executed) to perform functions described herein.

(151) The processor **1335** may include an intelligent hardware device, (e.g., a general-purpose processor, a DSP, a CPU, a microcontroller, an ASIC, an FPGA, a programmable logic device, a discrete gate or transistor logic component, a discrete hardware component, or any combination thereof). In some cases, the processor **1335** may be configured to operate a memory array using a memory controller. In other cases, a memory controller may be integrated into the processor **1335**. The processor **1335** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **1325**) to cause the device **1305** to perform various functions (e.g., functions or tasks supporting feedback schemes for multiple component carrier scheduling and joint feedback reporting).

(152) FIG. **14** shows a block diagram **1400** of a device **1405** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The device **1405** may be an example of aspects of a base station **105** as described herein. The device **1405** may include a receiver **1410**, a communication manager **1415**, and a transmitter **1420**. The device **1405** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(153) The receiver **1410** may receive information such as packets, user data, or control information associated with various information channels (e.g., control channels, data channels, and information related to feedback schemes for multiple component carrier scheduling and joint feedback reporting, etc.). Information may be passed on to other components of the device **1405**. The receiver **1410** may be an example of aspects of the transceiver **1720** described with reference to FIG. **17**. The receiver **1410** may utilize a single antenna or a set of antennas.

(154) The communication manager **1415** may transmit, during a PMO, a first DCI scheduling a UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier, transmit, during the PMO, a second DCI scheduling the UE for a third PDSCH resource on the second component carrier, receive feedback for at least the first PDSCH resource, the second PDSCH resource, and the third PDSCH resource on a PUCCH, identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and decode the feedback based on the set of DAIs. The communication manager **1415** may also transmit, to a UE during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, transmit, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, receive feedback for the one or more first PDSCH resources and the one or more second PDSCH resources on a PUCCH, identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and decode the feedback based on the set of DAIs. The communication manager **1415** may be an example of aspects of the

communication manager **1710** described herein.

(155) The communication manager **1415**, or its sub-components, may be implemented in hardware, code (e.g., software or firmware) executed by a processor, or any combination thereof. If implemented in code executed by a processor, the functions of the communication manager **1415**, or its sub-components may be executed by a general-purpose processor, a DSP, an application-specific integrated circuit (ASIC), a FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described in the present disclosure.

(156) The communication manager **1415**, or its sub-components, may be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations by one or more physical components. In some examples, the communication manager **1415**, or its sub-components, may be a separate and distinct component in accordance with various aspects of the present disclosure. In some examples, the communication manager **1415**, or its sub-components, may be combined with one or more other hardware components, including but not limited to an I/O component, a transceiver, a network server, another computing device, one or more other components described in the present disclosure, or a combination thereof in accordance with various aspects of the present disclosure.

(157) By including or configuring the communication manager **1415** in accordance with examples described herein, the device **1405** (e.g., a processor controlling or otherwise coupled to the receiver **1410**, the transmitter **1420**, the communication manager **1415**, or a combination thereof) may support techniques for more efficient utilization of communication resources based on transmitting joint feedback for multiple DCI.

(158) The transmitter **1420** may transmit signals generated by other components of the device **1405**. In some examples, the transmitter **1420** may be collocated with a receiver **1410** in a transceiver module. For example, the transmitter **1420** may be an example of aspects of the transceiver **1720** described with reference to FIG. 17. The transmitter **1420** may utilize a single antenna or a set of antennas.

(159) FIG. 15 shows a block diagram **1500** of a device **1505** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The device **1505** may be an example of aspects of a device **1405**, or a base station **105** as described herein. The device **1505** may include a receiver **1510**, a communication manager **1515**, and a transmitter **1545**. The device **1505** may also include a processor. Each of these components may be in communication with one another (e.g., via one or more buses).

(160) The receiver **1510** may receive information such as packets, user data, or control information associated with various information channels (e.g., control channels, data channels, and information related to feedback schemes for multiple component carrier scheduling and joint feedback reporting, etc.). Information may be passed on to other components of the device **1505**. The receiver **1510** may be an example of aspects of the transceiver **1720** described with reference to FIG. 17. The receiver **1510** may utilize a single antenna or a set of antennas.

(161) The communication manager **1515** may be an example of aspects of the communication manager **1415** as described herein. The communication manager **1515** may include a multi-CC scheduling component **1520**, a PDSCH scheduling component **1525**, a feedback receiving component **1530**, a DAI identifying component **1535**, and a feedback decoding component **1540**. The communication manager **1515** may be an example of aspects of the communication manager **1710** described herein.

(162) The multi-CC scheduling component **1520** may transmit, during a PMO, a first DCI scheduling a UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier. The multi-CC scheduling component **1520** may transmit, to a UE during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a

first CORESET pool index.

(163) The PDSCH scheduling component **1525** may transmit, during the PMO, a second DCI scheduling the UE for a third PDSCH resource on the second component carrier. The PDSCH scheduling component **1525** may transmit, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index.

(164) The feedback decoding component **1540** may decode the feedback based on the set of DAIs.

(165) The DAI identifying component **1535** may identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers. The DAI identifying component **1535** may identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier.

(166) The feedback receiving component **1530** may receive feedback for at least the first PDSCH resource, the second PDSCH resource, and the third PDSCH resource on a PUCCH. The feedback receiving component **1530** may receive feedback for the one or more first PDSCH resources and the one or more second PDSCH resources on a PUCCH.

(167) The transmitter **1545** may transmit signals generated by other components of the device **1505**. In some examples, the transmitter **1545** may be collocated with a receiver **1510** in a transceiver module. For example, the transmitter **1545** may be an example of aspects of the transceiver **1720** described with reference to FIG. 17. The transmitter **1545** may utilize a single antenna or a set of antennas.

(168) FIG. 16 shows a block diagram **1600** of a communication manager **1605** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The communication manager **1605** may be an example of aspects of a communication manager **1415**, a communication manager **1515**, or a communication manager **1710** described herein. The communication manager **1605** may include a multi-CC scheduling component **1610**, a PDSCH scheduling component **1615**, a feedback receiving component **1620**, a DAI identifying component **1625**, a feedback decoding component **1630**, a DAI ordering component **1635**, and a UE capability component **1640**. Each of these modules may communicate, directly or indirectly, with one another (e.g., via one or more buses).

(169) The multi-CC scheduling component **1610** may transmit, during a PMO, a first DCI scheduling a UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier. In some examples, the multi-CC scheduling component **1610** may transmit, to a UE during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index.

(170) The PDSCH scheduling component **1615** may transmit, during the PMO, a second DCI scheduling the UE for a third PDSCH resource on the second component carrier. In some examples, the PDSCH scheduling component **1615** may transmit, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index. In some examples, the PDSCH scheduling component **1615** may determine the one or more first DCI allocate one or more third PDSCH resources on a second component carrier.

(171) The feedback receiving component **1620** may receive feedback for at least the first PDSCH resource, the second PDSCH resource, and the third PDSCH resource on a PUCCH. In some examples, the feedback receiving component **1620** may receive feedback for the one or more first PDSCH resources and the one or more second PDSCH resources on a PUCCH.

(172) The DAI identifying component **1625** may identify a set of DAIS for the first DCI and the second DCI, where the first DCI has one or more DAIS whose values are based on the first DCI

scheduling PDSCH resources on different component carriers. In some examples, the DAI identifying component **1625** may identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier. In some examples, the DAI identifying component **1625** may determine a first associated component carrier index for the first DCI based on a highest component carrier index of the first component carrier and the second component carrier.

(173) In some examples, the DAI identifying component **1625** may determine a first associated component carrier index for the first DCI based on a lowest component carrier index of the first component carrier and the second component carrier. In some examples, the DAI identifying component **1625** may determine a first associated component carrier index for the first DCI and a second associated component carrier index for the second DCI are a same associated component carrier index based on the second PDSCH resource and the third PDSCH resource being scheduled on the second component carrier. In some examples, the DAI identifying component **1625** may determine a first DAI for the first DCI and a second DAI for the second DCI based on a time domain order of the second PDSCH resource and the third PDSCH resource, where the feedback is decoded based on the first DAI and the second DAI.

(174) In some examples, the DAI identifying component **1625** may determine a first DAI for the first DCI corresponds to a first component carrier index associated with the first component carrier based on the first PDSCH resource. In some examples, the DAI identifying component **1625** may determine a second DAI for the second DCI corresponds to a second component carrier index associated with the second component carrier based on the third PDSCH resource, where the feedback is decoded based on the first DAI and the second DAI. In some examples, the DAI identifying component **1625** may determine an ordering for the set of DAIs based on a temporal ordering of the PDSCH resources associated with a same CORESET pool index on the same component carrier scheduled during the PMO, then based on a CORESET pool index ordering on the same component carrier scheduled during the PMO, then based on a component carrier index ordering for the PMO, then based on a PMO ordering.

(175) In some examples, the DAI identifying component **1625** may determine an ordering for the set of DAIs based on a CORESET pool index ordering for the PDSCH resources having a common starting resource in a time domain on the same common component carrier scheduled during the PMO, then based on a temporal ordering of the PDSCH resources on the same component carrier scheduled during the PMO, then based on a component carrier index ordering for component carriers scheduled during the PMO, then based on a PMO index ordering.

(176) The feedback decoding component **1630** may decode the feedback based on the set of DAIs. In some examples, the feedback decoding component **1630** may identify feedback values for the set of ACK or NACK bits of a first DAI associated with the first DCI based on the first DCI scheduling a set of PDSCH resources, each of the set of ACK or NACK bits of the first DAI corresponding to a different one of the first PDSCH resource and the second PDSCH resource. In some examples, the feedback decoding component **1630** may identify a first feedback value for a first bit of the set of ACK or NACK bits of a second DAI associated with the second DCI based on the second DCI scheduling a single PDSCH resource. In some examples, the feedback decoding component **1630** may identify a NACK for a second bit of the set of ACK or NACK bits of the second DAI associated with the second DCI.

(177) The DAI ordering component **1635** may determine a first DAI for the first DCI associated with the first component carrier and the first PDSCH resource. In some examples, the DAI ordering component **1635** may determine a second DAI for the first DCI associated with the second component carrier and the second PDSCH resource. In some examples, the DAI ordering component **1635** may determine a third DAI for the second DCI associated with the second component carrier and the third PDSCH resource, where the feedback is decoded based on the first

DAI, the second DAI, and the third DAI. In some examples, the DAI ordering component **1635** may transmit, during the PMO, a third DCI scheduling the UE for a fourth PDSCH resource on the first component carrier. In some examples, the DAI ordering component **1635** may determine a fourth DAI for the third DCI associated with the first component carrier and the fourth PDSCH resource, where the fourth DAI and the first DAI are based on a temporal ordering of the first PDSCH resource and the fourth PDSCH resource, and where the feedback is decoded based on the fourth DAI.

(178) The UE capability component **1640** may receive, from the UE, a UE capability associated with a number of PDSCH resources per PMO per cell, the number of PDSCH resources per PMO per cell, or both.

(179) FIG. **17** shows a diagram of a system **1700** including a device **1705** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The device **1705** may be an example of or include the components of device **1405**, device **1505**, or a base station **105** as described herein. The device **1705** may include components for bi-directional voice and data communications including components for transmitting and receiving communications, including a communication manager **1710**, a network communications manager **1715**, a transceiver **1720**, an antenna **1725**, memory **1730**, a processor **1740**, and an inter-station communications manager **1745**. These components may be in electronic communication via one or more buses (e.g., bus **1750**).

(180) The communication manager **1710** may transmit, during a PMO, a first DCI scheduling a UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier, transmit, during the PMO, a second DCI scheduling the UE for a third PDSCH resource on the second component carrier, receive feedback for at least the first PDSCH resource, the second PDSCH resource, and the third PDSCH resource on a PUCCH, identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers, and decode the feedback based on the set of DAIs. The communication manager **1710** may also transmit, to a UE during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index, transmit, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index, receive feedback for the one or more first PDSCH resources and the one or more second PDSCH resources on a PUCCH, identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier, and decode the feedback based on the set of DAIs.

(181) The network communications manager **1715** may manage communications with the core network (e.g., via one or more wired backhaul links). For example, the network communications manager **1715** may manage the transfer of data communications for client devices, such as one or more UEs **115**.

(182) The transceiver **1720** may communicate bi-directionally, via one or more antennas, wired, or wireless links as described above. For example, the transceiver **1720** may represent a wireless transceiver and may communicate bi-directionally with another wireless transceiver. The transceiver **1720** may also include a modem to modulate the packets and provide the modulated packets to the antennas for transmission, and to demodulate packets received from the antennas.

(183) In some cases, the wireless device may include a single antenna **1725**. However, in some cases the device may have more than one antenna **1725**, which may be capable of concurrently transmitting or receiving multiple wireless transmissions.

(184) The memory **1730** may include RAM and ROM. The memory **1730** may store computer-

readable, computer-executable code **1735** including instructions that, when executed, cause the processor to perform various functions described herein. In some cases, the memory **1730** may contain, among other things, a BIOS which may control basic hardware or software operation such as the interaction with peripheral components or devices.

(185) The code **1735** may include instructions to implement aspects of the present disclosure, including instructions to support wireless communications. The code **1735** may be stored in a non-transitory computer-readable medium such as system memory or other type of memory. In some cases, the code **1735** may not be directly executable by the processor **1740** but may cause a computer (e.g., when compiled and executed) to perform functions described herein.

(186) The processor **1740** may include an intelligent hardware device, (e.g., a general-purpose processor, a DSP, a CPU, a microcontroller, an ASIC, an FPGA, a programmable logic device, a discrete gate or transistor logic component, a discrete hardware component, or any combination thereof). In some cases, the processor **1740** may be configured to operate a memory array using a memory controller. In other cases, a memory controller may be integrated into the processor **1740**. The processor **1740** may be configured to execute computer-readable instructions stored in a memory (e.g., the memory **1730**) to cause the device **1705** to perform various functions (e.g., functions or tasks supporting feedback schemes for multiple component carrier scheduling and joint feedback reporting).

(187) The inter-station communications manager **1745** may manage communications with other base station **105**, and may include a controller or scheduler for controlling communications with UEs **115** in cooperation with other base stations **105**. For example, the inter-station communications manager **1745** may coordinate scheduling for transmissions to UEs **115** for various interference mitigation techniques such as beamforming or joint transmission. In some examples, the inter-station communications manager **1745** may provide an X2 interface within an LTE/LTE-A wireless communication network technology to provide communication between base stations **105**.

(188) FIG. **18** shows a flowchart illustrating a method **1800** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The operations of method **1800** may be implemented by a UE **115** or its components as described herein. For example, the operations of method **1800** may be performed by a communication manager as described with reference to FIGS. **10** through **13**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally or alternatively, a UE may perform aspects of the described functions using special-purpose hardware.

(189) At **1805**, the UE may receive, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier. The operations of **1805** may be performed according to the methods described herein. In some examples, aspects of the operations of **1805** may be performed by a multi-CC scheduling component as described with reference to FIGS. **10** through **13**.

(190) At **1810**, the UE may receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier. The operations of **1810** may be performed according to the methods described herein. In some examples, aspects of the operations of **1810** may be performed by a PDSCH scheduling component as described with reference to FIGS. **10** through **13**.

(191) At **1815**, the UE may identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers. The operations of **1815** may be performed according to the methods described herein. In some examples, aspects of the operations of **1815** may be performed by a DAI identifying component as described with reference to FIGS. **10** through **13**.

(192) At **1820**, the UE may transmit feedback based on the set of DAIs. The operations of **1820**

may be performed according to the methods described herein. In some examples, aspects of the operations of **1820** may be performed by a feedback transmitting component as described with reference to FIGS. **10** through **13**.

(193) FIG. **19** shows a flowchart illustrating a method **1900** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The operations of method **1900** may be implemented by a UE **115** or its components as described herein. For example, the operations of method **1900** may be performed by a communication manager as described with reference to FIGS. **10** through **13**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally or alternatively, a UE may perform aspects of the described functions using special-purpose hardware.

(194) At **1905**, the UE may receive, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier. The operations of **1905** may be performed according to the methods described herein. In some examples, aspects of the operations of **1905** may be performed by a multi-CC scheduling component as described with reference to FIGS. **10** through **13**.

(195) At **1910**, the UE may receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier. The operations of **1910** may be performed according to the methods described herein. In some examples, aspects of the operations of **1910** may be performed by a PDSCH scheduling component as described with reference to FIGS. **10** through **13**.

(196) At **1915**, the UE may determine a first associated component carrier index for the first DCI based on a highest component carrier index of the first component carrier and the second component carrier. The operations of **1915** may be performed according to the methods described herein. In some examples, aspects of the operations of **1915** may be performed by a DAI identifying component as described with reference to FIGS. **10** through **13**.

(197) At **1920**, the UE may identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers. The operations of **1920** may be performed according to the methods described herein. In some examples, aspects of the operations of **1920** may be performed by a DAI identifying component as described with reference to FIGS. **10** through **13**.

(198) At **1925**, the UE may transmit feedback based on the set of DAIs. The operations of **1925** may be performed according to the methods described herein. In some examples, aspects of the operations of **1925** may be performed by a feedback transmitting component as described with reference to FIGS. **10** through **13**.

(199) FIG. **20** shows a flowchart illustrating a method **2000** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The operations of method **2000** may be implemented by a UE **115** or its components as described herein. For example, the operations of method **2000** may be performed by a communication manager as described with reference to FIGS. **10** through **13**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally or alternatively, a UE may perform aspects of the described functions using special-purpose hardware.

(200) At **2005**, the UE may receive, from a base station during a PMO, first DCI scheduling the UE for a first PDSCH resource on a first component carrier and for a second PDSCH resource on a second component carrier. The operations of **2005** may be performed according to the methods described herein. In some examples, aspects of the operations of **2005** may be performed by a multi-CC scheduling component as described with reference to FIGS. **10** through **13**.

(201) At **2010**, the UE may receive, during the PMO, second DCI scheduling the UE for a third PDSCH resource on the second component carrier. The operations of **2010** may be performed

according to the methods described herein. In some examples, aspects of the operations of **2010** may be performed by a PDSCH scheduling component as described with reference to FIGS. **10** through **13**.

(202) At **2015**, the UE may determine that a first associated component carrier index for the first DCI and a second associated component carrier index for the second DCI are a same associated component carrier index based on the second PDSCH resource and the third PDSCH resource being scheduled on the second component carrier. The operations of **2015** may be performed according to the methods described herein. In some examples, aspects of the operations of **2015** may be performed by a DAI identifying component as described with reference to FIGS. **10** through **13**.

(203) At **2020**, the UE may identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers. The operations of **2020** may be performed according to the methods described herein. In some examples, aspects of the operations of **2020** may be performed by a DAI identifying component as described with reference to FIGS. **10** through **13**.

(204) At **2025**, the UE may determine a first DAI for the first DCI and a second DAI for the second DCI based on a time domain order of the second PDSCH resource and the third PDSCH resource. The operations of **2025** may be performed according to the methods described herein. In some examples, aspects of the operations of **2025** may be performed by a DAI identifying component as described with reference to FIGS. **10** through **13**.

(205) At **2030**, the UE may transmit feedback based on the set of DAIs. The operations of **2030** may be performed according to the methods described herein. In some examples, aspects of the operations of **2030** may be performed by a feedback transmitting component as described with reference to FIGS. **10** through **13**.

(206) FIG. **21** shows a flowchart illustrating a method **2100** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The operations of method **2100** may be implemented by a base station **105** or its components as described herein. For example, the operations of method **2100** may be performed by a communication manager as described with reference to FIGS. **14** through **17**. In some examples, a base station may execute a set of instructions to control the functional elements of the base station to perform the described functions. Additionally or alternatively, a base station may perform aspects of the described functions using special-purpose hardware.

(207) At **2105**, the base station may transmit, during a PMO, a first DCI scheduling a UE for a first PDSCH resource on a first component carrier and a second PDSCH resource on a second component carrier. The operations of **2105** may be performed according to the methods described herein. In some examples, aspects of the operations of **2105** may be performed by a multi-CC scheduling component as described with reference to FIGS. **14** through **17**.

(208) At **2110**, the base station may transmit, during the PMO, a second DCI scheduling the UE for a third PDSCH resource on the second component carrier. The operations of **2110** may be performed according to the methods described herein. In some examples, aspects of the operations of **2110** may be performed by a PDSCH scheduling component as described with reference to FIGS. **14** through **17**.

(209) At **2115**, the base station may receive feedback for at least the first PDSCH resource, the second PDSCH resource, and the third PDSCH resource on a PUCCH. The operations of **2115** may be performed according to the methods described herein. In some examples, aspects of the operations of **2115** may be performed by a feedback receiving component as described with reference to FIGS. **14** through **17**.

(210) At **2120**, the base station may identify a set of DAIs for the first DCI and the second DCI, where the first DCI has one or more DAIs whose values are based on the first DCI scheduling PDSCH resources on different component carriers. The operations of **2120** may be performed

according to the methods described herein. In some examples, aspects of the operations of **2120** may be performed by a DAI identifying component as described with reference to FIGS. **14** through **17**.

(211) At **2125**, the base station may decode the feedback based on the set of DAIs. The operations of **2125** may be performed according to the methods described herein. In some examples, aspects of the operations of **2125** may be performed by a feedback decoding component as described with reference to FIGS. **14** through **17**.

(212) FIG. **22** shows a flowchart illustrating a method **2200** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The operations of method **2200** may be implemented by a UE **115** or its components as described herein. For example, the operations of method **2200** may be performed by a communication manager as described with reference to FIGS. **10** through **13**. In some examples, a UE may execute a set of instructions to control the functional elements of the UE to perform the described functions. Additionally or alternatively, a UE may perform aspects of the described functions using special-purpose hardware.

(213) At **2205**, the UE may receive, from a base station during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index. The operations of **2205** may be performed according to the methods described herein. In some examples, aspects of the operations of **2205** may be performed by a multi-CC scheduling component as described with reference to FIGS. **10** through **13**.

(214) At **2210**, the UE may receive, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index. The operations of **2210** may be performed according to the methods described herein. In some examples, aspects of the operations of **2210** may be performed by a PDSCH scheduling component as described with reference to FIGS. **10** through **13**.

(215) At **2215**, the UE may identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier. The operations of **2215** may be performed according to the methods described herein. In some examples, aspects of the operations of **2215** may be performed by a DAI identifying component as described with reference to FIGS. **10** through **13**.

(216) At **2220**, the UE may transmit feedback based on the set of DAIs. The operations of **2220** may be performed according to the methods described herein. In some examples, aspects of the operations of **2220** may be performed by a feedback component as described with reference to FIGS. **10** through **13**.

(217) FIG. **23** shows a flowchart illustrating a method **2300** that supports feedback schemes for multiple component carrier scheduling and joint feedback reporting in accordance with aspects of the present disclosure. The operations of method **2300** may be implemented by a base station **105** or its components as described herein. For example, the operations of method **2300** may be performed by a communication manager as described with reference to FIGS. **14** through **17**. In some examples, a base station may execute a set of instructions to control the functional elements of the base station to perform the described functions. Additionally or alternatively, a base station may perform aspects of the described functions using special-purpose hardware.

(218) At **2305**, the base station may transmit, to a UE during a PMO, one or more first DCI scheduling the UE for a corresponding one or more first PDSCH resources on a first component carrier, the one or more first DCI associated with a first CORESET pool index. The operations of **2305** may be performed according to the methods described herein. In some examples, aspects of the operations of **2305** may be performed by a multi-CC scheduling component as described with

reference to FIGS. 14 through 17.

(219) At **2310**, the base station may transmit, during the PMO, one or more second DCI scheduling the UE for a corresponding one or more second PDSCH resources on the first component carrier, the one or more second DCI associated with a second CORESET pool index. The operations of **2310** may be performed according to the methods described herein. In some examples, aspects of the operations of **2310** may be performed by a PDSCH scheduling component as described with reference to FIGS. 14 through 17.

(220) At **2315**, the base station may receive feedback for the one or more first PDSCH resources and the one or more second PDSCH resources on a PUCCH. The operations of **2315** may be performed according to the methods described herein. In some examples, aspects of the operations of **2315** may be performed by a feedback receiving component as described with reference to FIGS. 14 through 17.

(221) At **2320**, the base station may identify a set of DAIs for the one or more first DCI and the one or more second DCI, where values of the set of DAIs are based on the one or more first DCI and the one or more second DCI both scheduling PDSCH resources on a same component carrier. The operations of **2320** may be performed according to the methods described herein. In some examples, aspects of the operations of **2320** may be performed by a DAI identifying component as described with reference to FIGS. 14 through 17.

(222) At **2325**, the base station may decode the feedback based on the set of DAIs. The operations of **2325** may be performed according to the methods described herein. In some examples, aspects of the operations of **2325** may be performed by a feedback decoding component as described with reference to FIGS. 14 through 17.

(223) Aspect 1: A method for wireless communications at a UE, comprising: receiving, from a base station during a physical downlink control channel monitoring occasion, first downlink control information scheduling the UE for a first physical downlink shared channel resource on a first component carrier and for a second physical downlink shared channel resource on a second component carrier; receiving, during the physical downlink control channel monitoring occasion, second downlink control information scheduling the UE for a third physical downlink shared channel resource on the second component carrier; identifying a plurality of downlink assignment indices for the first downlink control information and the second downlink control information, wherein the first downlink control information has one or more downlink assignment indices whose values are based at least in part on the first downlink control information scheduling physical downlink shared channel resources on different component carriers; and transmitting feedback based at least in part on the plurality of downlink assignment indices.

(224) Aspect 2: The method of aspect 1, wherein identifying the plurality of downlink assignment indices further comprises: determining a first associated component carrier index for the first downlink control information based at least in part on a highest component carrier index of the first component carrier and the second component carrier.

(225) Aspect 3: The method of aspect 1, wherein identifying the plurality of downlink assignment indices further comprises: determining a first associated component carrier index for the first downlink control information based at least in part on a lowest component carrier index of the first component carrier and the second component carrier.

(226) Aspect 4: The method of any of aspects 1 to 3, wherein identifying the plurality of downlink assignment indices further comprises: determining that a first associated component carrier index for the first downlink control information and a second associated component carrier index for the second downlink control information are a same associated component carrier index based at least in part on the second physical downlink shared channel resource and the third physical downlink shared channel resource being scheduled on the second component carrier; and determining a first downlink assignment index for the first downlink control information and a second downlink assignment index for the second downlink control information based at least in part on a time

domain order of the second physical downlink shared channel resource and the third physical downlink shared channel resource.

(227) Aspect 5: The method of aspects 1 to 4, wherein identifying the plurality of downlink assignment indices further comprises: determining a first downlink assignment index for the first downlink control information corresponds to a first component carrier index associated with the first component carrier based at least in part on the first physical downlink shared channel resource; and determining a second downlink assignment index for the second downlink control information corresponds to a second component carrier index associated with the second component carrier based at least in part on the third physical downlink shared channel resource.

(228) Aspect 6: The method of any of aspects 1 to 5, wherein identifying the plurality of downlink assignment indices further comprises: determining a first downlink assignment index for the first downlink control information associated with the first component carrier and the first physical downlink shared channel resource; determining a second downlink assignment index for the first downlink control information associated with the second component carrier and the second physical downlink shared channel resource; and determining a third downlink assignment index for the second downlink control information associated with the second component carrier and the third physical downlink shared channel resource.

(229) Aspect 7: The method of aspect 6, wherein the second downlink assignment index and the third downlink assignment index are based at least in part on a temporal ordering of the second physical downlink shared channel resource and the third physical downlink shared channel resource.

(230) Aspect 8: The method of any of aspects 1 to 7, further comprising: receiving, during the physical downlink control channel monitoring occasion, a third downlink control information scheduling the UE for a fourth physical downlink shared channel resource on the first component carrier.

(231) Aspect 9: The method of aspect 8, wherein identifying the plurality of downlink assignment indices further comprises: determining a fourth downlink assignment index for the third downlink control information associated with the first component carrier and the fourth physical downlink shared channel resource, wherein the fourth downlink assignment index and the first downlink assignment index are based at least in part on a temporal ordering of the first physical downlink shared channel resource and the fourth physical downlink shared channel resource.

(232) Aspect 10: The method of any of aspects 1 to 9, further comprising: generating a hybrid automatic repeat request acknowledgment codebook whose order is based at least in part on the plurality of downlink assignment indices.

(233) Aspect 11: The method of any of aspects 1 to 10, further comprising: determining a plurality of acknowledgment or negative acknowledgment bits for each downlink assignment index of the plurality of downlink assignment indices.

(234) Aspect 12: The method of aspect 11, further comprising: determining feedback values for the plurality of acknowledgment or negative acknowledgment bits of a first downlink assignment index associated with the first downlink control information based at least in part on the first downlink control information scheduling a plurality of physical downlink shared channel resources, each of the plurality of acknowledgment or negative acknowledgment bits of the first downlink assignment index corresponding to a different one of the first physical downlink shared channel resource and the second physical downlink shared channel resource.

(235) Aspect 13: The method of aspect 11, further comprising: determining a first feedback value for a first bit of the plurality of acknowledgment or negative acknowledgment bits of a second downlink assignment index associated with the second downlink control information based at least in part on the second downlink control information scheduling a single physical downlink shared channel resource; and including a negative acknowledgment for a second bit of the plurality of acknowledgment or negative acknowledgment bits of the second downlink assignment index

associated with the second downlink control information.

(236) Aspect 14: The method of any of aspects 1 to 13, wherein the plurality of downlink assignment indices are ordered first based at least in part on ascending order of an associated serving cell index with downlink control information in a given physical downlink control channel monitoring occasion then based at last in part on ascending order of physical downlink control channel monitoring occasion index.

(237) Aspect 15: A method for wireless communications at a base station, comprising: transmitting, during a physical downlink control channel monitoring occasion, a first downlink control information scheduling a UE for a first physical downlink shared channel resource on a first component carrier and a second physical downlink shared channel resource on a second component carrier; transmitting, during the physical downlink control channel monitoring occasion, a second downlink control information scheduling the UE for a third physical downlink shared channel resource on the second component carrier; receiving feedback for at least the first physical downlink shared channel resource, the second physical downlink shared channel resource, and the third physical downlink shared channel resource on a physical uplink control channel; identifying a plurality of downlink assignment indices for the first downlink control information and the second downlink control information, wherein the first downlink control information has one or more downlink assignment indices whose values are based at least in part on the first downlink control information scheduling physical downlink shared channel resources on different component carriers; and decoding the feedback based at least in part on the plurality of downlink assignment indices.

(238) Aspect 16: The method of aspect 15, wherein identifying the plurality of downlink assignment indices further comprises: determining a first associated component carrier index for the first downlink control information based at least in part on a highest component carrier index of the first component carrier and the second component carrier.

(239) Aspect 17: The method of aspect 15, wherein identifying the plurality of downlink assignment indices further comprises: determining a first associated component carrier index for the first downlink control information based at least in part on a lowest component carrier index of the first component carrier and the second component carrier.

(240) Aspect 18: The method of any of aspects 15 to 17, wherein identifying the plurality of downlink assignment indices further comprises: determining a first associated component carrier index for the first downlink control information and a second associated component carrier index for the second downlink control information are a same associated component carrier index based at least in part on the second physical downlink shared channel resource and the third physical downlink shared channel resource being scheduled on the second component carrier; and determining a first downlink assignment index for the first downlink control information and a second downlink assignment index for the second downlink control information based at least in part on a time domain order of the second physical downlink shared channel resource and the third physical downlink shared channel resource, wherein the feedback is decoded based at least in part on the first downlink assignment index and the second downlink assignment index.

(241) Aspect 19: The method of any of aspects 15 to 18, wherein identifying the plurality of downlink assignment indices further comprises: determining a first downlink assignment index for the first downlink control information corresponds to a first component carrier index associated with the first component carrier based at least in part on the first physical downlink shared channel resource; and determining a second downlink assignment index for the second downlink control information corresponds to a second component carrier index associated with the second component carrier based at least in part on the third physical downlink shared channel resource, wherein the feedback is decoded based at least in part on the first downlink assignment index and the second downlink assignment index.

(242) Aspect 20: The method of any of aspects 15 to 19, further comprising: determining a first

downlink assignment index for the first downlink control information associated with the first component carrier and the first physical downlink shared channel resource; determining a second downlink assignment index for the first downlink control information associated with the second component carrier and the second physical downlink shared channel resource; and determining a third downlink assignment index for the second downlink control information associated with the second component carrier and the third physical downlink shared channel resource, wherein the feedback is decoded based at least in part on the first downlink assignment index, the second downlink assignment index, and the third downlink assignment index.

(243) Aspect 21: The method of aspect 20, wherein the second downlink assignment index and the third downlink assignment index are based at least in part on a temporal ordering of the second physical downlink shared channel resource and the third physical downlink shared channel resource.

(244) Aspect 22: The method of any of aspects 20 or 21, further comprising: transmitting, during the physical downlink control channel monitoring occasion, a third downlink control information scheduling the UE for a fourth physical downlink shared channel resource on the first component carrier.

(245) Aspect 23: The method of aspect 22, wherein identifying the plurality of downlink assignment indices further comprises: determining a fourth downlink assignment index for the third downlink control information associated with the first component carrier and the fourth physical downlink shared channel resource, wherein the fourth downlink assignment index and the first downlink assignment index are based at least in part on a temporal ordering of the first physical downlink shared channel resource and the fourth physical downlink shared channel resource, and wherein the feedback is decoded based at least in part on the fourth downlink assignment index.

(246) Aspect 24: The method of any of aspects 15 to 23, wherein the feedback includes a hybrid automatic repeat request acknowledgment codebook whose order is generated based at least in part on the plurality of downlink assignment indices.

(247) Aspect 25: The method of any of aspects 15 to 24, wherein the feedback includes a plurality of acknowledgment or negative acknowledgment bits for each downlink assignment index of the plurality of downlink assignment indices.

(248) Aspect 26: The method of aspect 25, wherein decoding the feedback comprises: identifying feedback values for the plurality of acknowledgment or negative acknowledgment bits of a first downlink assignment index associated with the first downlink control information based at least in part on the first downlink control information scheduling a plurality of physical downlink shared channel resources, each of the plurality of acknowledgment or negative acknowledgment bits of the first downlink assignment index corresponding to a different one of the first physical downlink shared channel resource and the second physical downlink shared channel resource.

(249) Aspect 27: The method of aspect 25, wherein decoding the feedback comprises: identifying a first feedback value for a first bit of the plurality of acknowledgment or negative acknowledgment bits of a second downlink assignment index associated with the second downlink control information based at least in part on the second downlink control information scheduling a single physical downlink shared channel resource; and identifying a negative acknowledgment for a second bit of the plurality of acknowledgment or negative acknowledgment bits of the second downlink assignment index associated with the second downlink control information.

(250) Aspect 28: The method of any of aspects 15 to 27, wherein the plurality of downlink assignment indices are ordered first based at least in part on ascending order of an associated serving cell index with downlink control information in a corresponding physical downlink control channel monitoring occasion then based at last in part on ascending order of physical downlink control channel monitoring occasion index.

(251) Aspect 29: A method for wireless communications at a UE, comprising: receiving, from a base station during a physical downlink control channel monitoring occasion, one or more first

downlink control information scheduling the UE for a corresponding one or more first physical downlink shared channel resources on a first component carrier, the one or more first downlink control information associated with a first control resource set pool index; receiving, during the physical downlink control channel monitoring occasion, one or more second downlink control information scheduling the UE for a corresponding one or more second physical downlink shared channel resources on the first component carrier, the one or more second downlink control information associated with a second control resource set pool index; identifying a plurality of downlink assignment indices for the one or more first downlink control information and the one or more second downlink control information, wherein values of the plurality of downlink assignment indices are based at least in part on the one or more first downlink control information and the one or more second downlink control information both scheduling physical downlink shared channel resources on a same component carrier; and transmitting feedback based at least in part on the plurality of downlink assignment indices.

(252) Aspect 30: The method of aspect 29, further comprising transmitting, to a base station, a UE capability associated with a number of physical downlink shared channel resources per physical downlink control channel monitoring occasion per cell, the number of physical downlink shared channel resources per physical downlink control channel monitoring occasion per cell, or both.

(253) Aspect 31: The method of any of aspects 29 or 30, wherein identifying the plurality of downlink assignment indices further comprises: determining an ordering for the plurality of downlink assignment indices based at least in part on a temporal ordering of the physical downlink shared channel resources associated with a same control resource set pool index on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a control resource set pool index ordering on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a component carrier index ordering for the physical downlink control channel monitoring occasion, then based at least in part on a physical downlink control channel monitoring occasion ordering.

(254) Aspect 32: The method of any of aspects 29 or 30, wherein identifying the plurality of downlink assignment indices further comprises: determining an ordering for the plurality of downlink assignment indices based at least in part on a control resource set pool index ordering for the physical downlink shared channel resources having a common starting resource in a time domain on the same common component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a temporal ordering of the physical downlink shared channel resources on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a component carrier index ordering for component carriers scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a physical downlink control channel monitoring occasion index ordering.

(255) Aspect 33: The method of any of aspects 29 to 32, wherein the one or more first downlink control information and the one or more second downlink control information include up to a maximum number of downlink control information.

(256) Aspect 34: The method of any of aspects 29 to 33, wherein the maximum number of downlink control information is twice a value indicated by the UE.

(257) Aspect 35: The method of any of aspects 29 to 34, wherein the maximum number of downlink control information is indicated by the UE, wherein a first physical downlink shared channel resource and a second physical downlink shared channel resource have a same starting resource in a time domain.

(258) Aspect 36: The method of any of aspects 29 to 35, further comprising: determining the one or more first downlink control information allocate one or more third physical downlink shared channel resources in a second component carrier.

(259) Aspect 37: The method of any of aspects 29 to 36, wherein the first control resource set pool index corresponds to a first transmission and reception point, and the second control resource set pool index corresponds to a second transmission and reception point.

(260) Aspect 38: The method of any of aspects 29 to 37, wherein an ordering for the plurality of downlink assignment indices is based at least in part on a physical downlink shared channel resource start time ordering, a control resource set pool index ordering, a component carrier index ordering, a monitoring occasion index ordering, or any combination thereof.

(261) Aspect 39: A method for wireless communications at a base station, comprising: transmitting, to a UE during a physical downlink control channel monitoring occasion, one or more first downlink control information scheduling the UE for a corresponding one or more first physical downlink shared channel resources on a first component carrier, the one or more first downlink control information associated with a first control resource set pool index; transmitting, during the physical downlink control channel monitoring occasion, one or more second downlink control information scheduling the UE for a corresponding one or more second physical downlink shared channel resources on the first component carrier, the one or more second downlink control information associated with a second control resource set pool index; receiving feedback for the one or more first physical downlink shared channel resources and the one or more second physical downlink shared channel resources on a physical uplink control channel; identifying a plurality of downlink assignment indices for the one or more first downlink control information and the one or more second downlink control information, wherein values of the plurality of downlink assignment indices are based at least in part on the one or more first downlink control information and the one or more second downlink control information both scheduling physical downlink shared channel resources on a same component carrier; and decoding the feedback based at least in part on the plurality of downlink assignment indices.

(262) Aspect 40: The method of aspect 39, further comprising: receiving, from the UE, a UE capability associated with a number of physical downlink shared channel resources per physical downlink control channel monitoring occasion per cell, the number of physical downlink shared channel resources per physical downlink control channel monitoring occasion per cell, or both.

(263) Aspect 41: The method of any of aspects 39 or 40, wherein identifying the plurality of downlink assignment indices further comprises: determining an ordering for the plurality of downlink assignment indices based at least in part on a temporal ordering of the physical downlink shared channel resources associated with a same control resource set pool index on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a control resource set pool index ordering on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a component carrier index ordering for the physical downlink control channel monitoring occasion, then based at least in part on a physical downlink control channel monitoring occasion ordering.

(264) Aspect 42: The method of any of aspects 39 or 40, wherein identifying the plurality of downlink assignment indices further comprises: determining an ordering for the plurality of downlink assignment indices based at least in part on a control resource set pool index ordering for the physical downlink shared channel resources having a common starting resource in a time domain on the same common component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a temporal ordering of the physical downlink shared channel resources on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a component carrier index ordering for component carriers scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a physical downlink control channel monitoring occasion index ordering.

(265) Aspect 43: The method of any of aspects 39 to 42, wherein the one or more first downlink

control information and the one or more second downlink control information include up to a maximum number of downlink control information instances based.

(266) Aspect 44: The method of any of aspects 39 to 43, wherein the maximum number of downlink control information is twice a value indicated by the UE.

(267) Aspect 45: The method of any of aspects 39 to 44, wherein the maximum number of downlink control information is indicated by the UE, wherein a first physical downlink shared channel resource and a second physical downlink shared channel resource have a same starting resource in a time domain.

(268) Aspect 46: The method of any of aspects 39 to 45, further comprising: determining the one or more first downlink control information allocate one or more third physical downlink shared channel resources on a second component carrier.

(269) Aspect 47: The method of any of aspects 39 to 46, wherein the first control resource set pool index corresponds to a first transmission and reception point, and the second control resource set pool index corresponds to a second transmission and reception point.

(270) It should be noted that the methods described herein describe possible implementations, and that the operations and the steps may be rearranged or otherwise modified and that other implementations are possible. Further, aspects from two or more of the methods may be combined.

(271) Although aspects of an LTE, LTE-A, LTE-A Pro, or NR system may be described for purposes of example, and LTE, LTE-A, LTE-A Pro, or NR terminology may be used in much of the description, the techniques described herein are applicable beyond LTE, LTE-A, LTE-A Pro, or NR networks. For example, the described techniques may be applicable to various other wireless communications systems such as Ultra Mobile Broadband (UMB), Institute of Electrical and Electronics Engineers (IEEE) 802.11 (Wi-Fi), IEEE 802.16 (WiMAX), IEEE 802.20, Flash-OFDM, as well as other systems and radio technologies not explicitly mentioned herein.

(272) Information and signals described herein may be represented using any of a variety of different technologies and techniques. For example, data, instructions, commands, information, signals, bits, symbols, and chips that may be referenced throughout the description may be represented by voltages, currents, electromagnetic waves, magnetic fields or particles, optical fields or particles, or any combination thereof.

(273) The various illustrative blocks and components described in connection with the disclosure herein may be implemented or performed with a general-purpose processor, a DSP, an ASIC, a CPU, an FPGA or other programmable logic device, discrete gate or transistor logic, discrete hardware components, or any combination thereof designed to perform the functions described herein. A general-purpose processor may be a microprocessor, but in the alternative, the processor may be any processor, controller, microcontroller, or state machine. A processor may also be implemented as a combination of computing devices (e.g., a combination of a DSP and a microprocessor, multiple microprocessors, one or more microprocessors in conjunction with a DSP core, or any other such configuration).

(274) The functions described herein may be implemented in hardware, software executed by a processor, firmware, or any combination thereof. If implemented in software executed by a processor, the functions may be stored on or transmitted over as one or more instructions or code on a computer-readable medium. Other examples and implementations are within the scope of the disclosure and appended claims. For example, due to the nature of software, functions described herein may be implemented using software executed by a processor, hardware, firmware, hardwiring, or combinations of any of these. Features implementing functions may also be physically located at various positions, including being distributed such that portions of functions are implemented at different physical locations.

(275) Computer-readable media includes both non-transitory computer storage media and communication media including any medium that facilitates transfer of a computer program from one place to another. A non-transitory storage medium may be any available medium that may be

accessed by a general-purpose or special-purpose computer. By way of example, and not limitation, non-transitory computer-readable media may include RAM, ROM, electrically erasable programmable ROM (EEPROM), flash memory, compact disk (CD) ROM or other optical disk storage, magnetic disk storage or other magnetic storage devices, or any other non-transitory medium that may be used to carry or store desired program code means in the form of instructions or data structures and that may be accessed by a general-purpose or special-purpose computer, or a general-purpose or special-purpose processor. Also, any connection is properly termed a computer-readable medium. For example, if the software is transmitted from a website, server, or other remote source using a coaxial cable, fiber optic cable, twisted pair, digital subscriber line (DSL), or wireless technologies such as infrared, radio, and microwave, then the coaxial cable, fiber optic cable, twisted pair, DSL, or wireless technologies such as infrared, radio, and microwave are included in the definition of computer-readable medium. Disk and disc, as used herein, include CD, laser disc, optical disc, digital versatile disc (DVD), floppy disk and Blu-ray disc where disks usually reproduce data magnetically, while discs reproduce data optically with lasers.

Combinations of the above are also included within the scope of computer-readable media.

(276) As used herein, including in the claims, “or” as used in a list of items (e.g., a list of items prefaced by a phrase such as “at least one of” or “one or more of”) indicates an inclusive list such that, for example, a list of at least one of A, B, or C means A or B or C or AB or AC or BC or ABC (i.e., A and B and C). Also, as used herein, the phrase “based on” shall not be construed as a reference to a closed set of conditions. For example, an example step that is described as “based on condition A” may be based on both a condition A and a condition B without departing from the scope of the present disclosure. In other words, as used herein, the phrase “based on” shall be construed in the same manner as the phrase “based at least in part on.”

(277) In the appended figures, similar components or features may have the same reference label. Further, various components of the same type may be distinguished by following the reference label by a dash and a second label that distinguishes among the similar components. If just the first reference label is used in the specification, the description is applicable to any one of the similar components having the same first reference label irrespective of the second reference label, or other subsequent reference label.

(278) The description set forth herein, in connection with the appended drawings, describes example configurations and does not represent all the examples that may be implemented or that are within the scope of the claims. The term “example” used herein means “serving as an example, instance, or illustration,” and not “preferred” or “advantageous over other examples.” The detailed description includes specific details for the purpose of providing an understanding of the described techniques. These techniques, however, may be practiced without these specific details. In some instances, known structures and devices are shown in block diagram form in order to avoid obscuring the concepts of the described examples.

(279) The description herein is provided to enable a person having ordinary skill in the art to make or use the disclosure. Various modifications to the disclosure will be apparent to a person having ordinary skill in the art, and the generic principles defined herein may be applied to other variations without departing from the scope of the disclosure. Thus, the disclosure is not limited to the examples and designs described herein, but is to be accorded the broadest scope consistent with the principles and novel features disclosed herein.

Claims

1. A method for wireless communications at a user equipment (UE), comprising: receiving, during a physical downlink control channel monitoring occasion, a first downlink control information message scheduling the UE for a first physical downlink shared channel resource on a first component carrier and for a second physical downlink shared channel resource on a second

component carrier; receiving, during the physical downlink control channel monitoring occasion, a second downlink control information message scheduling the UE for a third physical downlink shared channel resource on the second component carrier; identifying a plurality of downlink assignment indices including a first downlink assignment index in the first downlink control information message and a second downlink assignment index in the second downlink control information message; identifying a first associated component carrier index for the first downlink control information message and a second associated component carrier index for the second downlink control information message, wherein values of the first downlink assignment index and the second downlink assignment index are ordered in increasing order of physical downlink shared channel reception starting time based at least in part on the first downlink control information message and the second downlink control information message having a same associated component carrier index; and transmitting feedback based at least in part on the plurality of downlink assignment indices.

2. The method of claim 1, wherein identifying the plurality of downlink assignment indices further comprises: determining the first associated component carrier index for the first downlink control information message based at least in part on a highest component carrier index of the first component carrier and the second component carrier.

3. The method of claim 1, wherein identifying the plurality of downlink assignment indices further comprises: determining the first associated component carrier index for the first downlink control information message based at least in part on a lowest component carrier index of the first component carrier and the second component carrier.

4. The method of claim 1, wherein identifying the plurality of downlink assignment indices further comprises: determining the first downlink assignment index for the first downlink control information message corresponds to the first associated component carrier index associated with the first component carrier based at least in part on the first physical downlink shared channel resource; and determining the second downlink assignment index for the second downlink control information message corresponds to the second associated component carrier index associated with the second component carrier based at least in part on the third physical downlink shared channel resource.

5. The method of claim 1, wherein identifying the plurality of downlink assignment indices further comprises: determining the first downlink assignment index for the first downlink control information message associated with the first component carrier and the first physical downlink shared channel resource; determining a third downlink assignment index for the first downlink control information message associated with the second component carrier and the second physical downlink shared channel resource; and determining the second downlink assignment index for the second downlink control information message associated with the second component carrier and the third physical downlink shared channel resource.

6. The method of claim 5, further comprising: receiving, during the physical downlink control channel monitoring occasion, a third downlink control information message scheduling the UE for a fourth physical downlink shared channel resource on the first component carrier.

7. The method of claim 6, wherein identifying the plurality of downlink assignment indices further comprises: determining a fourth downlink assignment index for the third downlink control information message associated with the first component carrier and the fourth physical downlink shared channel resource, wherein the fourth downlink assignment index and the first downlink assignment index are based at least in part on a temporal ordering of the first physical downlink shared channel resource and the fourth physical downlink shared channel resource.

8. The method of claim 1, further comprising: generating a hybrid automatic repeat request acknowledgment codebook whose order is based at least in part on the plurality of downlink assignment indices.

9. The method of claim 1, further comprising: determining a plurality of acknowledgment or

negative acknowledgment bits for each downlink assignment index of the plurality of downlink assignment indices.

10. The method of claim 9, further comprising: determining feedback values for the plurality of acknowledgment or negative acknowledgment bits of the first downlink assignment index associated with the first downlink control information message based at least in part on the first downlink control information message scheduling a plurality of physical downlink shared channel resources, each of the plurality of acknowledgment or negative acknowledgment bits of the first downlink assignment index corresponding to a different one of the first physical downlink shared channel resource and the second physical downlink shared channel resource.

11. The method of claim 9, further comprising: determining a first feedback value for a first bit of the plurality of acknowledgment or negative acknowledgment bits of the second downlink assignment index associated with the second downlink control information message based at least in part on the second downlink control information message scheduling a single physical downlink shared channel resource; and including a negative acknowledgment for a second bit of the plurality of acknowledgment or negative acknowledgment bits of the second downlink assignment index associated with the second downlink control information message.

12. The method of claim 1, wherein the plurality of downlink assignment indices are ordered first based at least in part on ascending order of an associated serving cell index with downlink control information in a given physical downlink control channel monitoring occasion then based at least in part on ascending order of physical downlink control channel monitoring occasion index.

13. A method for wireless communications at a user equipment (UE), comprising: transmitting an indication of a quantity of physical downlink shared channel resources that are schedulable per physical downlink control channel monitoring occasion per cell; receiving, during a physical downlink control channel monitoring occasion, one or more first downlink control information scheduling the UE for a corresponding one or more first physical downlink shared channel resources on a first component carrier in accordance with the quantity of physical downlink shared channel resources, the one or more first downlink control information associated with a first control resource set pool index; receiving, during the physical downlink control channel monitoring occasion, one or more second downlink control information scheduling the UE for a corresponding one or more second physical downlink shared channel resources on the first component carrier in accordance with the quantity of physical downlink shared channel resources, the one or more second downlink control information associated with a second control resource set pool index; identifying a plurality of downlink assignment indices for the one or more first downlink control information and the one or more second downlink control information, wherein values of the plurality of downlink assignment indices are based at least in part on the one or more first downlink control information and the one or more second downlink control information both scheduling physical downlink shared channel resources on a same component carrier; and transmitting feedback based at least in part on the plurality of downlink assignment indices.

14. The method of claim 13, wherein the indication comprises a UE capability associated with the quantity of physical downlink shared channel resources per physical downlink control channel monitoring occasion per cell.

15. The method of claim 13, wherein identifying the plurality of downlink assignment indices further comprises: determining an ordering for the plurality of downlink assignment indices based at least in part on a temporal ordering of the physical downlink shared channel resources associated with a same control resource set pool index on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a control resource set pool index ordering on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a component carrier index ordering for the physical downlink control channel monitoring occasion, then based at least in part on a physical downlink control channel monitoring occasion ordering.

16. The method of claim 13, wherein identifying the plurality of downlink assignment indices further comprises: determining an ordering for the plurality of downlink assignment indices based at least in part on a control resource set pool index ordering for the physical downlink shared channel resources having a common starting resource in a time domain on a same common component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a temporal ordering of the physical downlink shared channel resources on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a component carrier index ordering for component carriers scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a physical downlink control channel monitoring occasion index ordering.

17. The method of claim 13, wherein the one or more first downlink control information and the one or more second downlink control information include up to a maximum number of downlink control information.

18. The method of claim 17, wherein the maximum number of downlink control information is twice a value indicated by the UE.

19. The method of claim 17, wherein the maximum number of downlink control information is indicated by the UE, wherein a first physical downlink shared channel resource and a second physical downlink shared channel resource have a same starting resource in a time domain.

20. The method of claim 13, further comprising: determining the one or more first downlink control information allocate one or more third physical downlink shared channel resources in a second component carrier.

21. The method of claim 13, wherein the first control resource set pool index corresponds to a first transmission and reception point, and the second control resource set pool index corresponds to a second transmission and reception point.

22. The method of claim 13, wherein an ordering for the plurality of downlink assignment indices is based at least in part on a physical downlink shared channel resource start time ordering, a control resource set pool index ordering, a component carrier index ordering, a monitoring occasion index ordering, or any combination thereof.

23. An apparatus for wireless communications at a user equipment (UE), comprising: at least one processor; at least one memory coupled with the at least one processor; and instructions stored in the at least one memory and executable by the at least one processor to cause the apparatus to: receive, during a physical downlink control channel monitoring occasion, a first downlink control information message scheduling the UE for a first physical downlink shared channel resource on a first component carrier and for a second physical downlink shared channel resource on a second component carrier; receive, during the physical downlink control channel monitoring occasion, a second downlink control information message scheduling the UE for a third physical downlink shared channel resource on the second component carrier; identify a plurality of downlink assignment indices including a first downlink assignment index in the first downlink control information message and a second downlink assignment index in the second downlink control information message; identify a first associated component carrier index for the first downlink control information message and a second associated component carrier index for the second downlink control information message, wherein values of the first downlink assignment index and the second downlink assignment index are ordered in increasing order of physical downlink shared channel reception starting time based at least in part on the first downlink control information message and the second downlink control information message having a same associated component carrier index; and transmit feedback based at least in part on the plurality of downlink assignment indices.

24. The apparatus of claim 23, wherein the instructions to identify the plurality of downlink assignment indices are further executable by the at least one processor to cause the apparatus to: determine the first associated component carrier index for the first downlink control information

message based at least in part on a highest component carrier index of the first component carrier and the second component carrier.

25. The apparatus of claim 23, wherein the instructions to identify the plurality of downlink assignment indices are further executable by the at least one processor to cause the apparatus to: determine the first associated component carrier index for the first downlink control information message based at least in part on a lowest component carrier index of the first component carrier and the second component carrier.

26. An apparatus for wireless communications at a user equipment (UE), comprising: at least one processor; at least one memory coupled with the at least one processor; and instructions stored in the at least one memory and executable by the at least one processor to cause the apparatus to: transmitting an indication of a quantity of physical downlink shared channel resources that are schedulable per physical downlink control channel monitoring occasion per cell; receive, during a physical downlink control channel monitoring occasion, one or more first downlink control information scheduling the UE for a corresponding one or more first physical downlink shared channel resources on a first component carrier in accordance with the quantity of physical downlink shared channel resources, the one or more first downlink control information associated with a first control resource set pool index; receive, during the physical downlink control channel monitoring occasion, one or more second downlink control information scheduling the UE for a corresponding one or more second physical downlink shared channel resources on the first component carrier in accordance with the quantity of physical downlink shared channel resources, the one or more second downlink control information associated with a second control resource set pool index; identify a plurality of downlink assignment indices for the one or more first downlink control information and the one or more second downlink control information, wherein values of the plurality of downlink assignment indices are based at least in part on the one or more first downlink control information and the one or more second downlink control information both scheduling physical downlink shared channel resources on a same component carrier; and transmit feedback based at least in part on the plurality of downlink assignment indices.

27. The apparatus of claim 26, wherein the indication comprises a UE capability associated with the quantity of downlink shared channel resources per monitoring occasion per cell.

28. The apparatus of claim 26, wherein the instructions to identify the plurality of downlink assignment indices are further executable by the at least one processor to cause the apparatus to: determine an ordering for the plurality of downlink assignment indices based at least in part on a temporal ordering of the physical downlink shared channel resources associated with a same control resource set pool index on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a control resource set pool index ordering on the same component carrier scheduled during the physical downlink control channel monitoring occasion, then based at least in part on a component carrier index ordering for the physical downlink control channel monitoring occasion, then based at least in part on a physical downlink control channel monitoring occasion ordering.
