

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12400065
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Kao; Chen-Yuan et al.

Capture IR drop analyzer and analyzing method thereof

Abstract

A capture IR drop analyzer and an analyzing method thereof are provided. The capture IR drop analyzing method includes: receiving circuit layout information and package model information of a circuit; analyzing a plurality of circuit blocks respectively corresponding to a plurality of bump current sources according to the circuit layout information and the package model information; calculating at least one critical circuit block according to each of the bump current sources and a current demand value of each of the corresponding circuit blocks; and analyzing a clock tree architecture of the at least one critical circuit block to obtain design structure adjustment information.

Inventors: Kao; Chen-Yuan (Hsinchu, TW), Tsai; Min-Hsiu (Hsinchu, TW)

Applicant: Global Unichip Corporation (Hsinchu, TW); Taiwan Semiconductor Manufacturing Company, Ltd. (Hsinchu, TW)

Family ID: 1000008781825

Assignee: Global Unichip Corporation (Hsinchu, TW); Taiwan Semiconductor Manufacturing Company, Ltd. (Hsinchu, TW)

Appl. No.: 17/844083

Filed: June 20, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230342536 A1	Oct. 26, 2023

Foreign Application Priority Data

TW	111115335	Apr. 22, 2022
----	-----------	---------------

Publication Classification

Int. Cl.: G06F30/396 (20200101); G06F30/34 (20200101); G06F30/398 (20200101)

U.S. Cl.:

CPC G06F30/396 (20200101); G06F30/34 (20200101); G06F30/398 (20200101);

Field of Classification Search

USPC: 716/111

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9881120	12/2017	Ginetti	N/A	G06F 30/367
2003/0151100	12/2002	Toyoshima	257/E27.098	H10B 10/00
2004/0243952	12/2003	Croix	716/108	G06F 30/367
2011/0270598	12/2010	Zou	716/103	G06F 30/367
2014/0365148	12/2013	Tehranipoor	702/60	G01R 31/318364
2019/0220560	12/2018	Chhabra	N/A	G01R 21/133
2023/0342536	12/2022	Kao	N/A	G06F 30/398

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
583760	12/2003	TW	N/A
I472004	12/2014	TW	N/A
202143086	12/2020	TW	N/A

OTHER PUBLICATIONS

“Office Action of Taiwan Counterpart Application”, issued on Mar. 28, 2023, p. 1-p. 6. cited by applicant

Primary Examiner: Alam; Mohammed

Attorney, Agent or Firm: JCIPRNET

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATION

(1) This application claims the priority benefit of Taiwan application serial no. 111115335, filed on Apr. 22, 2022. The entirety of the above-mentioned patent application is hereby incorporated by reference herein and made a part of this specification.

BACKGROUND OF THE INVENTION

Field of the Invention

(2) The invention relates to a capture IR drop analyzer and an analyzing method thereof, and more particularly, to a capture IR drop analyzer and an analyzing method thereof capable of reducing analyzing time.

Description of Related Art

(3) In circuit design, IR drop often causes abnormal circuit operation. In the past, there has been no specific mitigation plans for capture voltage drop, and the IR analysis is usually too time-consuming, and the provided vector is not representative, which makes it impossible to comprehensively analyze the capture IR drop for the circuit.

SUMMARY OF THE INVENTION

(4) The invention provides a capture IR drop analyzer and an analyzing method thereof that may effectively obtain design structure adjustment information of a circuit.

(5) A capture IR drop analyzing method of the invention includes: receiving circuit layout information and package model information of a circuit; analyzing a plurality of circuit blocks respectively corresponding to a plurality of bump current sources according to the circuit layout information and the package model information; calculating at least one critical circuit block according to each of the bump current sources and a current demand value of each of the corresponding circuit blocks; and analyzing a clock tree architecture of the at least one critical circuit block to obtain design structure adjustment information.

(6) A capture IR drop analyzer of the invention includes a transmission interface and a controller. The transmission interface is configured to receive circuit layout information and package model information of a circuit. The controller is coupled to the transmission interface and configured to: analyze a plurality of circuit blocks respectively corresponding to a plurality of bump current sources according to the circuit layout information and the package model information; calculate at least one critical circuit block according to each of the bump current sources and a current demand value of each of the corresponding circuit blocks; and analyze a clock tree architecture of the at least one critical circuit block to obtain design structure adjustment information.

(7) Based on the above, the analyzing method of capture IR drop of an embodiment of the invention may avoid the time-consuming voltage drop analysis operation by defining the high risk area of the capture voltage drop on the circuit, and may comprehensively evaluate the voltage drop risk in the capture mode of the circuit scan chain.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 shows a flowchart of an analyzing method of capture IR drop of an embodiment of the invention.

(2) FIG. 2 shows a flowchart of an analyzing method of capture IR drop of another embodiment of the invention.

(3) FIG. 3 and FIG. 4 show schematic diagrams of an embodiment of a modeling operation of a bump current source.

(4) FIG. 5 shows a waveform diagram of current demand of a circuit element under a clock tree architecture in a circuit block.

(5) FIG. 6 shows a flowchart of a critical circuit block identification operation of an embodiment of the invention.

(6) FIG. 7A to FIG. 7C respectively show a clock tree architecture of a circuit element in a critical circuit block contributing a large current peak value and a schematic diagram of correspondingly generated design structure adjustment information of an embodiment of the invention.

(7) FIG. 8 shows a schematic diagram of a capture IR drop analyzer of an embodiment of the

invention.

DESCRIPTION OF THE EMBODIMENTS

(8) Referring to FIG. 1, FIG. 1 shows a flowchart of an analyzing method of capture IR drop of an embodiment of the invention. In particular, in step **S110**, circuit layout information and package model information of a circuit are received. In particular, the package model information is a circuit netlist with resistance, capacitance, and inductance information. In the present embodiment, the receiving action of the circuit layout information may be performed by receiving a file in DEF (Design Exchange Format) format or a file in LEF (Library Exchange Format) format. Next, in step **S120**, a plurality of circuit blocks respectively corresponding to a plurality of bump current sources in the circuit may be analyzed according to the received circuit layout information and package model information. In particular, a plurality of bump current sources may be included in the circuit. In particular, each of the bump current sources may be configured to drive corresponding circuit blocks. The driven circuit blocks may include a plurality of registers, and these registers may respectively belong to one or a plurality of clock tree architectures.

(9) In step **S130**, next, each of the bump current sources is analyzed, and at least one critical circuit block is calculated according to each of the bump current sources and the current demand value of each of the corresponding circuit blocks. In particular, in the present embodiment, the calculation may be performed one by one for the current demand value of each of the circuit blocks corresponding to each of the bump current sources. Moreover, current demand values that are too large are found, so as to set the corresponding one or plurality of circuit blocks as critical circuit blocks.

(10) Further, in step **S140**, the clock tree architecture of the one or plurality of critical circuit blocks is analyzed to obtain design structure adjustment information.

(11) In the present embodiment, the design structure adjustment information may be configured to allow the designer to adjust the circuit architecture of the critical circuit blocks of a circuit, and may also be configured as a basis for setting constraint conditions for electronic design automation (EDA) applications such as automatic test pattern generation (ATPG).

(12) In the present embodiment, according to the design structure adjustment information, the current demand values of the critical circuit blocks in the circuit may be reduced, and the influence of the capture IR drop on circuit performance may be reduced. Moreover, the analysis method of capture IR drop of the present embodiment may analyze the critical circuit blocks in the circuit, and in the full-scale analysis of the circuit, a design structure adjustment strategy may be quickly calculated for the critical circuit blocks to effectively improve the efficiency of circuit design.

(13) Referring to FIG. 2, FIG. 2 shows a flowchart of an analyzing method of capture IR drop of another embodiment of the invention. In particular, circuit layout information **A1** and package model information **A2** of files in DEF (Design Exchange Format) or files in LEF (Library Exchange Format) may be received. Next, in step **S210**, the modeling operation of a bump current source in the circuit may be performed according to the circuit layout information **A1** and the package model information **A2**. For details, please refer to FIG. 3 and FIG. 4 showing schematic diagrams of an embodiment of a modeling operation of bump current sources. In FIG. 3, the modeling action of the bump current sources may be performed via a current calculator **310** to calculate the current supply state of each of the bump current sources according to the circuit layout information **A1**, the package model information **A2** and an assumption protocol **P1**. In particular, in FIG. 4, a circuit **400** has a plurality of bump current sources **410** to **419**. The bump current sources **410** to **419** are disposed at a plurality of positions of the circuit **400**. The plurality of bump current sources **410** to **419** respectively supply the working currents of the plurality of circuit blocks, and each of the circuit blocks includes a plurality of registers, and these registers may belong to one or a plurality of different clock tree architectures. Taking the bump current source **410** as an example, the circuit block corresponding to the bump current source **410** has a plurality of registers **REG1** to **REG3**, and the registers **REG1** to **REG3** may respectively belong to three different clock tree

architectures.

(14) The current calculator **310** may calculate the current demand value of each of the registers **REG1** to **REG3**, and calculate the current demand value of the circuit block corresponding to the bump current source **410**. The current calculator **310** may be implemented by a controller with computing capability. Here, please refer to FIG. 5 showing a waveform diagram of current demand of a circuit element under a clock tree architecture in a circuit block. In particular, a waveform **510** represents the working current generated by the register corresponding to the clock signal in the clock tree architecture; a waveform **520** represents the working current generated by the combinational logic circuit; a waveform **530** represents the working current generated by data transmission and reception; and a waveform **540** is the sum of the working currents of the waveforms **510** to **530**.

(15) It should be mentioned that, the assumption protocol **P1** received by the current calculator **310** is a clock signal of a preset clock tree architecture and an action protocol for data transmission and reception, such as a toggle rate of the clock signal. Via the calculation of various demand currents, the current calculator **310** may generate a current information IFO, wherein the current information IFO includes a plurality of current demand values corresponding to each of the bump current sources **410** to **419** under the condition of different toggle rates of the clock signal.

(16) In the present embodiment, the current information IFO may be stored in a memory and form a look-up table.

(17) Referring again to FIG. 2, following step **S210**, a critical circuit block clock analysis is performed in step **S220**. In particular, according to the current information IFO obtained in step **S210**, the identification action of critical circuit blocks may be performed. Here, referring to FIG. 6, FIG. 6 shows a flowchart of a critical circuit block identification operation of an embodiment of the invention. In step **S610**, an analysis may be performed for a bump current source *i* (the *i*-th bump current source), wherein *i*=1 in the initial state. In step **S620**, whether the current demand value of the bump current source *i* is smaller than the reference threshold is determined. In particular, the reference threshold is one preset value used as a basis for determining whether the capture IR drop is too large.

(18) When the current demand value of the bump current source *i* is less than the reference threshold, the value of *i* is incremented by 1 and steps **S610** and **S620** are performed again to analyze the next bump current source *i*. When the current demand value of the bump current source *i* is not less than the reference threshold, the circuit block corresponding to the bump current source *i* may be set as a critical circuit block, and step **S630** is performed.

(19) In step **S630**, the action of current contributor identification may be performed for the critical circuit blocks. Moreover, circuit elements in the critical circuit blocks contributing a large current peak value to the bump current source *i* are found for identification. Next, in step **S640**, the architecture analysis operation of the clock tree is performed for the identified circuit elements contributing a large current peak value.

(20) In step **S650**, next, whether the analysis of the last bump current source is completed is determined. If not, the analysis action of the next bump current source is performed, and if yes, the entire action flow is ended.

(21) Referring to FIG. 2 again, following step **S220**, in step **S230**, a relevant strategy for reducing capture voltage drop may be obtained according to the clock tree architecture generated by the process of FIG. 6. In particular, referring to FIG. 7A to FIG. 7C, FIG. 7A to FIG. 7C respectively show a clock tree architecture of a circuit element in a critical circuit block contributing a large current peak value and a schematic diagram of correspondingly generated design structure adjustment information of an embodiment of the invention.

(22) In FIG. 7A, a clock tree architecture **710** corresponds to a clock signal **CLK1**. In the clock tree architecture **710**, integrated control gates (ICGs) **711** and **712** correspond to control registers **G1-1** and **G1-2**, respectively. In particular, when the two first quantities of the registers **G1-1** and **G1-2**

controlled by the ICGs **711** and **712** are both smaller than a preset reference value k , the correspondingly generated design structure adjustment information may be configured to add logic circuits **721** and **722** to control the ICGs **711** and **712**, respectively, and via the logic circuits **721** and **722**, the ICGs **711** and **712** are activated in a time-share manner, and a new clock tree architecture **710'** is generated.

(23) In FIG. 7B, a clock tree architecture **720** corresponds to a clock signal CLK2. In the clock tree architecture **720**, when a second quantity of a plurality of registers G2 not controlled by an ICG is greater than the preset reference value k , the correspondingly generated design structure adjustment information may be configured to split the registers G2 into registers G2-1 and G2-2 of a plurality of portions, and provide a plurality of auxiliary ICGs **741** and **742** to be respectively coupled between the clock signal CLK2 and the registers G2-1 and G2-2. Moreover, a new clock tree architecture **720'** is generated by adding a plurality of logic circuits **731** and **732** to be respectively coupled to the auxiliary ICGs **741** and **742** and control the auxiliary ICGs **741** and **742**. The logic circuits **731** and **732** are configured to enable the auxiliary ICGs **741** and **742** to be activated in a time-share manner.

(24) In FIG. 7C, a clock tree architecture **730** corresponds to a clock signal CLK3. In the clock tree architecture **730**, an ICG **751** corresponds to a control register G3. In particular, when the first quantity of the register G3 controlled by the ICG **751** is greater than the reference value k , the correspondingly generated design structure adjustment information may be configured to split the register G3 into a register G3-1 of the first portion and a register G3-2 of the second portion, and add ICGs **771** and **772** and logic circuits **761** and **762**. The ICGs **771** and **772** are coupled to the ICG **751** and respectively coupled to the registers G3-1 and G3-2, and generate a new clock tree architecture **730'**. The logic circuits **761** and **762** respectively control the ICGs **771** and **772** so that the ICGs **771** and **772** are activated in a time-share manner.

(25) Referring back to FIG. 2, according to the strategy for reducing capture voltage drop obtained in step S230, a design fixing plan A3 and an ATPG constraint plan A4 may be generated.

(26) Please refer to FIG. 8 below. FIG. 8 shows a schematic diagram of a capture IR drop analyzer of an embodiment of the invention. A capture IR drop analyzer **800** includes a transmission interface **820** and a controller **810**. The transmission interface **820** and the controller **810** are coupled to each other. The transmission interface **820** may be configured to receive circuit layout information and package model information of a circuit. The controller **810** may be configured to execute steps S120 to S140 shown in FIG. 1 and obtain design structure adjustment information.

(27) In the present embodiment, the controller **810** may be designed by a hardware description language (HDL) or any other design method of a digital circuit known to those having ordinary skill in the art, and is a hardware circuit implemented by a field-programmable gate array (FPGA), complex programmable logic device (CPLD), or application-specific integrated circuit (ASIC). The transmission interface **820** may be any form of wired or wireless communication interface known to those having ordinary skill in the art, and there is no specific limitation.

(28) Based on the above, in the invention, the critical circuit block is defined by analyzing the current demand value of each of the bump current sources. Moreover, a design structure adjustment analysis is performed for the high-risk area of capture voltage drop on the critical circuit block circuit to reduce the time needed for the voltage drop analysis operation, and the voltage drop risk in the capture mode of the circuit scan chain may be comprehensively evaluated.

Claims

1. An analyzing method of capture IR drop, comprising: receiving circuit layout information and package model information of a circuit; analyze, according to the circuit layout information and the package model information, a plurality of circuit blocks respectively corresponding to a plurality of bump current sources in the circuit; calculating at least one critical circuit block according to each

- of the bump current sources and a current demand value of each of the corresponding circuit blocks, comparing the current demand value of the bump current source with a reference threshold to set each of the plurality of circuit blocks as the at least one critical circuit block; and analyzing a clock tree architecture of the at least one critical circuit block to obtain design structure adjustment information.
2. The analyzing method of claim 1, wherein the step of calculating the at least one critical circuit block according to each of the bump current sources and the current demand value of each of the corresponding circuit blocks comprises: calculating a plurality of working currents of each of the circuit blocks, and generating the current demand value corresponding to each of the circuit blocks according to the working currents; and determining whether the current demand value of each of the circuit blocks is greater than the reference threshold, so as to set each of the circuit blocks as the at least one critical circuit block.
3. The analyzing method of claim 2, wherein the working currents comprise a first working current through which data passes through each of the circuit blocks; a second working current generated by a combinational logic circuit of each of the circuit blocks; and a third working current generated by each of the circuit blocks receiving a clock signal.
4. The analyzing method of claim 1, wherein the step of analyzing the at least one clock tree architecture of the at least one critical circuit block to obtain the design structure adjustment information comprises: analyzing, in the at least one clock tree architecture, each of a plurality of integrated control gates and a first quantity of a plurality of correspondingly controlled first registers and a second quantity of a plurality of second registers not controlled by an integrated control gate; and generating the design structure adjustment information according to a magnitude relationship between the first quantity and a reference value and according to a magnitude relationship between the second quantity and two reference values.
5. The analyzing method of claim 4, wherein when the first quantity is less than the reference value, the design structure adjustment information is provided to: add a plurality of logic circuits to respectively control the integrated control gates; and activate the integrated control gates in a time-share manner via the logic circuits.
6. The analyzing method of claim 4, wherein when the first quantity is greater than the reference value, the design structure adjustment information is provided to: add a plurality of auxiliary integrated control gates after each of the integrated control gates, wherein the first registers are divided into a plurality of portions and respectively coupled to the auxiliary integrated control gates; add a plurality of logic circuits to respectively control the auxiliary integrated control gates; and activate the auxiliary integrated control gates in a time-share manner via the logic circuits.
7. The analyzing method of claim 4, wherein when the second quantity is greater than the reference value, the design structure adjustment information is provided to: provide a plurality of auxiliary integrated control gates to be coupled between a clock signal and the second registers, wherein the second registers are divided into a plurality of portions and respectively coupled to the auxiliary integrated control gates; add a plurality of logic circuits to respectively control the auxiliary integrated control gates; and activate the auxiliary integrated control gates in a time-share manner via the logic circuits.
8. A capture IR drop analyzer, comprising: a transmission interface configured to receive circuit layout information and package model information of a circuit; and a controller coupled to the transmission interface, and configured to: analyze, according to the circuit layout information and the package model information, a plurality of circuit blocks respectively corresponding to a plurality of bump current sources in the circuit; calculate at least one critical circuit block according to each of the bump current sources and a current demand value of each of the corresponding circuit blocks, comparing the current demand value of the bump current source with a reference threshold to set each of the plurality of circuit blocks as the at least one critical circuit block; and analyze a clock tree architecture of the at least one critical circuit block to obtain design

structure adjustment information.

9. The capture IR drop analyzer of claim 8, wherein the controller is further configured to: calculate a plurality of working currents of each of the circuit blocks, and generate the current demand value corresponding to each of the circuit blocks according to the working currents; and determine whether the current demand value of each of the circuit blocks is greater than the reference threshold, so as to set each of the circuit blocks as the at least one critical circuit block.

10. The capture IR drop analyzer of claim 9, wherein the working currents comprise a first working current through which data passes through each of the circuit blocks; a second working current generated by a combinational logic circuit of each of the circuit blocks; and a third working current generated by each of the circuit blocks receiving a clock signal.

11. The capture IR drop analyzer of claim 8, wherein the controller is further configured to: analyze, in the at least one clock tree architecture, each of a plurality of integrated control gates and a first quantity of a plurality of correspondingly controlled first registers and a second quantity of a plurality of second registers not controlled by an integrated control gate; and generate the design structure adjustment information according to a magnitude relationship between the first quantity and a reference value and according to a magnitude relationship between the second quantity and two reference values.

12. The capture IR drop analyzer of claim 11, wherein when the first quantity is less than the reference value, the design structure adjustment information provided by the controller comprises: adding a plurality of logic circuits to respectively control the integrated control gates; and activating the integrated control gates in a time-share manner via the logic circuits.

13. The capture IR drop analyzer of claim 11, wherein when the first quantity is greater than the reference value, the design structure adjustment information provided by the controller comprises: adding a plurality of auxiliary integrated control gates after each of the integrated control gates, wherein the first registers are divided into a plurality of portions and respectively coupled to the auxiliary integrated control gates; adding a plurality of logic circuits to respectively control the auxiliary integrated control gates; and activating the auxiliary integrated control gates in a time-share manner via the logic circuits.

14. The capture IR drop analyzer of claim 11, wherein when the second quantity is greater than the reference value, the design structure adjustment information provided by the controller comprises: providing a plurality of auxiliary integrated control gates to be coupled between a clock signal and the second registers, wherein the second registers are divided into a plurality of portions and respectively coupled to the auxiliary integrated control gates; adding a plurality of logic circuits to respectively control the auxiliary integrated control gates; and activating the auxiliary integrated control gates in a time-share manner via the logic circuits.
