

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12399283
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Wilcox; Timothy A.

Methods and apparatus to manage correction requests in a positioning system

Abstract

Methods, apparatus, systems and articles of manufacture are disclosed to manage correction requests in a positioning system. Example apparatus disclosed herein includes accuracy determination circuitry to determine accuracy of a current position based on location data. The example apparatus includes correction request circuitry to request location correction data from a reference location when the accuracy does not satisfy a threshold. The example apparatus includes correction determination circuitry to adjust the location data with location correction data.

Inventors:	Wilcox; Timothy A. (Cissna Park, IL)
Applicant:	Deere & Company (Moline, IL)
Family ID:	1000008780973
Assignee:	Deere & Company (Moline, IL)
Appl. No.:	17/901666
Filed:	September 01, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230147323 A1	May. 11, 2023

Related U.S. Application Data

us-provisional-application US 63276344 20211105

Publication Classification

Int. Cl.: G01S19/48 (20100101); G01S19/07 (20100101); G01S19/04 (20100101); G01S19/39 (20100101); G01S19/40 (20100101)

U.S. Cl.:

CPC G01S19/48 (20130101); G01S19/07 (20130101); G01S19/04 (20130101); G01S19/071 (20190801); G01S19/396 (20190801); G01S19/40 (20130101)

Field of Classification Search

CPC: G01S (19/48); G01S (19/07); G01S (19/04); G01S (19/396); G01S (19/071); G01S (19/40)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
7562167	12/2008	Anderson	N/A	N/A
7679555	12/2009	Dai et al.	N/A	N/A
8587475	12/2012	Leandro	N/A	N/A
9426230	12/2015	Anderson	N/A	N/A
10234565	12/2018	Wilson et al.	N/A	N/A
2006/0046749	12/2005	Pomerantz	455/457	H04W 64/00
2009/0135057	12/2008	Vollath	342/357.27	G01S 19/32
2015/0045058	12/2014	Rudow	455/456.1	H04M 1/72457
2022/0357464	12/2021	Peng	N/A	G01S 19/396

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2005278069	12/2009	AU	N/A
107710017	12/2017	CN	G01S 19/426
1989567	12/2011	EP	N/A
2044457	12/2014	EP	N/A
2364454	12/2018	EP	N/A

OTHER PUBLICATIONS

Digifarm, "Digifarm VBN," retrieved from [<https://www.digifarm.com/faqs/>] on Dec. 7, 2019, 1 page. cited by applicant

Primary Examiner: Magloire; Vladimir

Assistant Examiner: Siddiquee; Ismaaeel A.

Attorney, Agent or Firm: HANLEY, FLIGHT & ZIMMERMAN, LLC

Background/Summary

RELATED APPLICATION (1) This patent claims the benefit of U.S. Provisional Patent Application No. 63/276,344, which was filed on Nov. 5, 2021. U.S. Provisional Patent Application No. 63/276,344 is hereby incorporated herein by reference in its entirety. Priority to U.S. Provisional Patent Application No. 63/276,344 is hereby claimed.

FIELD OF THE DISCLOSURE

(1) This disclosure relates generally to global navigation satellite systems, and, more particularly, methods and apparatus to manage correction requests in a positioning system.

BACKGROUND

(2) Real-time kinematic (RTK) positioning techniques are commonly used for improving position data from satellites that are used in global navigation satellite systems (GNSS). Global navigation satellite systems derive position data based on calculating distances between a receiver and different satellites from time measurements of signal transmissions from the respective satellites to the receiver. In global navigation satellite systems, the location of the receiver is calculated based on comparing the distances from the different satellites. RTK positioning techniques determine corrections for the position data from the satellites by calculating errors metrics based on a reference location.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) FIG. 1 is a schematic illustration of an example environment in which teaching of this disclosure may be implemented.

(2) FIG. 2 is a block diagram of example rover circuitry and example base circuitry included in the example environment of FIG. 1.

(3) FIG. 3 is a flowchart representative of machine readable instructions which may be executed to implement the example rover circuitry of FIGS. 1 and/or 2.

(4) FIG. 4 is a flowchart representative of machine readable instructions which may be executed to implement the example base circuitry of FIGS. 1 and/or 2.

(5) FIG. 5 is a block diagram of an example processing platform structured to execute the instructions of FIG. 3 to implement the example rover circuitry of FIGS. 1 and/or 2.

(6) FIG. 6 is a block diagram of an example processing platform structured to execute the instructions of FIG. 3 to implement the example base circuitry of FIGS. 1 and/or 2.

(7) FIG. 7 is a block diagram of an example implementation of the processor circuitry of FIGS. 5 and/or 6.

(8) FIG. 8 is a block diagram of another example implementation of the processor circuitry of FIGS. 5 and/or 6.

DETAILED DESCRIPTION

(9) The figures are not to scale. In general, the same reference numbers will be used throughout the drawing(s) and accompanying written description to refer to the same or like parts. As used herein, unless otherwise stated, the term “above” describes the relationship of two parts relative to Earth. A first part is above a second part, if the second part has at least one part between Earth and the first part. Likewise, as used herein, a first part is “below” a second part when the first part is closer to the Earth than the second part. As noted above, a first part can be above or below a second part with one or more of: other parts therebetween, without other parts therebetween, with the first and second parts touching, or without the first and second parts being in direct contact with one another. As used in this patent, stating that any part (e.g., a layer, film, area, region, or plate) is in any way on (e.g., positioned on, located on, disposed on, or formed on, etc.) another part, indicates that the referenced part is either in contact with the other part, or that the referenced part is above the other

part with one or more intermediate part(s) located therebetween. As used herein, connection references (e.g., attached, coupled, connected, and joined) may include intermediate members between the elements referenced by the connection reference and/or relative movement between those elements unless otherwise indicated. As such, connection references do not necessarily infer that two elements are directly connected and/or in fixed relation to each other.

(10) Unless specifically stated otherwise, descriptors such as “first,” “second,” “third,” etc. are used herein without imputing or otherwise indicating any meaning of priority, physical order, arrangement in a list, and/or ordering in any way, but are merely used as labels and/or arbitrary names to distinguish elements for ease of understanding the disclosed examples. In some examples, the descriptor “first” may be used to refer to an element in the detailed description, while the same element may be referred to in a claim with a different descriptor such as “second” or “third.” In such instances, it should be understood that such descriptors are used merely for identifying those elements distinctly that might, for example, otherwise share a same name. As used herein “substantially real time” refers to occurrence in a near instantaneous manner recognizing there may be real world delays for computing time, transmission, etc. Thus, unless otherwise specified, “substantially real time” refers to real time+/-1 second.

(11) Global navigation satellite systems (e.g., global positioning system (GPS), etc.) derive position data based on a receiver obtaining signals from a network of satellites. Global navigation satellite systems determine distances between the receiver and different satellites based on how long it takes for the receiver to receive signals from the respective satellites. In global navigation satellite systems, the location of the receiver is calculated based on comparing the distances from the different satellites. However, the location data determined by the global navigation satellite systems can grow increasing inaccurate based on signal processing delays, satellite clock errors, etc.

(12) Real-time kinematic (RTK) positioning is a technique commonly used for improving position data from satellites that are used in the global navigation satellite systems. The RTK positioning technique derives corrections for satellite-based positioning based on a known location of a reference station (e.g., a base). RTK positioning systems calculate corrections for respective satellites in the network by comparing the known location of the base to the location determined from the satellite-based calculations. The RTK corrections are broadcasted from the base to the GPS receivers (e.g., rovers).

(13) As the number of satellites increase in the constellation, RTK corrections for the growing number of satellites need to be broadcast between the base and a rover. An increase in the RTK corrections will require more data to be sent between base circuitry implemented at the base and rover circuitry implemented at the rover. In prior systems, RTK corrections were broadcasted from the base to rovers using radio modems. However, performance of GPS receivers have increased, allowing them to navigate further from an RTK base (conceivably up to 50 miles), which is well beyond the capabilities of currently utilized radios.

(14) In some examples, agricultural machines (e.g., tractors, etc.) use GPS systems to improve precision of farming activities (e.g., field mapping, farm planning, tractor guidance, soil sampling, etc.). In such examples, the agricultural machines include cellular modems for their GPS systems. In some examples, RTK corrections are delivered to the GPS receiver using the cellular modem. When the GPS is navigating using RTK, data is sent from the base circuitry to the rover circuitry at a constant frequency. In some examples, cellular products typically establish a continuous connection to either a virtual base station provider or directly to a data stream coming from a base. For agricultural uses, this communication typically consumes about 1 GB of data per month for each GPS.

(15) In some examples, GPS receivers are able to determine network corrections for positioning data without the use of RTK corrections. The GPS receivers can connect to a GPS correction network that provides corrections for positioning data to the GPS receivers that are included in the network. In some examples, the information of the GPS receivers are collected and monitored by

the GPS correction network. In some examples, the GPS correction network generate corrections for all satellites in constellation of satellites for the GPS systems. The GPS receivers connect to a correction stream from the GPS correction network to receive the corrections. Unlike the RTK corrections that are specific to GPS receivers in specific geographic locations, the corrections from the GPS correction network are relevant to the whole constellation of satellites and are not specific to the GPS receivers in specific geographic locations. GPS receivers are able to attain performance in the X-Y-Z planes that is acceptable in performance and indistinguishable to the performance of RTK based navigation using the corrections from the GPS correction network. In some examples, GPS receivers are able to determine and monitor the accuracy of the GPS solutions from the GPS correction network.

(16) Examples disclosed herein serve to control the amount of corrections sent to a GPS rover by using a set of criteria such as an acceptable error metric to only request RTK corrections from a base when they are needed. Examples disclosed herein obtain information that characterizes the accuracy or error of the GPS network corrections. Examples disclosed herein use this information to determine when communication with the base is necessary. Examples disclosed herein can request corrections continuously at startup to rapidly pull in an accurate position but then rely on a GPS network and/or other network based corrections to the largest extent possible until certain criteria are met (such as a configurable error metric is reached). In examples disclosed herein, the GPS requests the communications device (e.g., a user's cellular phone or integrated modem) to connect to the RTK correction stream and receive data until the error metric is reduced. In some examples, the amount of acceptable error could be application specific (e.g., guidance vs elevation control) or it could be based on the type of field operation that is being done (e.g., planting, tillage, etc.), or user configurable. In some examples, the communication device connects to the RTK correction stream when environmental conditions affect the error metric of the GPS. For example, if the machine containing the GPS drives under a tree, the GPS may lose communication with the satellite and/or the GPS correction network, which can cause an increase in the error of the location determined by the GPS. In such examples, the communication device connects to the RTK correction stream. In such examples, the communication device establishes a connection with the RTK correction stream to improve the accuracy of the position once the machine containing the GPS is no longer under the tree, and the communication device maintains the connection with the RTK correction stream until the error metric is reduced. In examples disclosed herein, the GPS monitors the inaccuracy of the solution and requests corrections only when it needs them, thus significantly reducing the amount of data that is required to navigate but insuring a minimum level of accuracy.

(17) FIG. 1 is a schematic illustration of an example environment **100** in which teaching of this disclosure may be implemented. The example environment includes an example rover **110** implementing example rover circuitry **112**, an example cell tower **115**, an example base **120** implementing example base circuitry **122**, and an example satellite **125**.

(18) The example rover circuitry **112** of the illustrated example of FIG. 1 determines current location data for a device associated with the rover circuitry **112** using the example satellite **125**. The rover circuitry **112** receives signals from the satellite **125**. The rover circuitry **112** determines the amount of time it took for the rover circuitry **112** to receive the signal from the satellite **125**. The rover circuitry **112** determines the current location data based on a calculated distance from the satellite **125** using the amount of time to receive the signal. In some examples, the rover circuitry **112** determines the accuracy of the current location data by calculating an error metric for the current location data. In some examples, the rover circuitry **112** compares the accuracy of the current location data to a threshold. In some examples, if the rover circuitry **112** determines the accuracy of the current location data does not satisfy the threshold, then the rover circuitry **112** connects to a correction stream to obtain location correction data from the example base circuitry **122**. An example implementation of the rover circuitry **112** is further described in detail below in

connection with FIG. 2. In some examples, the rover circuitry **112** obtains location correction data from the example base circuitry **122** through a short message service (SMS) message. In such examples, the rover circuitry **112** subscribes to a correction service (e.g., an application on a communication device) to receive corrections in a correction packet using an SMS message. However, other ways of obtaining the location correction data from the example base circuitry **122** may additionally and/or alternatively be used.

(19) The example cell tower **115** provides communication between the cellular modem on the example rover circuitry **112** and the cellular modem on the example base circuitry **122**. Additionally and/or alternatively, the example rover circuitry **112** and the example base circuitry **122** can communicate location correction data via a cloud. However, other ways of communicating over the cellular network between the rover circuitry **112** and the base circuitry **122** may additionally and/or alternatively be used. In some examples, the rover circuitry **112** and the base circuitry **122** can communicate over a local network (e.g., an infield network) that is dedicated to the exchange of RTK corrections.

(20) The example base circuitry **122** of the illustrated example of FIG. 1 determines location correction data for the example satellite **125**. The base circuitry **122** receives signals from the satellite **125**. The example location request circuitry **230** determines the location data for the base **120** using the received signals from the satellite **125**. The base circuitry **122** determines the amount of time it took for the base circuitry **122** to receive a signal from the satellite **125**. In some examples, the base circuitry **122** determines the location data of the base **120** based on a calculated distance from the position of the satellite **125** using the amount of time it took to receive the signal. In some examples, the base circuitry **122** compares the calculated location data to the known reference location of the base **120** and calculates an error value based on the comparison. In some examples, the base circuitry **122** provides the error value to the example rover circuitry **112** through the correction stream. In some examples, the base circuitry **122** provides the error value to the rover circuitry **112** through an SMS message using the cell tower **115**. An example implementation of the base circuitry **122** is further described in detail below in connection with FIG. 2.

(21) FIG. 2 is a block diagram of the example rover circuitry **112** and the example base circuitry **122** included in the example environment **100** of FIG. 1. The example rover circuitry **112** includes example location calculation circuitry **210**, example accuracy determination circuitry **215**, example correction request circuitry **220**, and example correction determination circuitry **225**. The example base circuitry **122** includes example location request circuitry **230**, example error calculation circuitry **235**, an example error database **240**, example request receiver circuitry **245**, and example correction transmission circuitry **250**.

(22) The example location calculation circuitry **210** of the illustrated example of FIG. 2 determines the current location data for the rover **110** of FIG. 1. In some examples, the location calculation circuitry **210** receives signals from the satellite **125**. The location calculation circuitry **210** determines the amount of time it took for the location calculation circuitry **210** to receive the signal from the satellite **125**. The location calculation circuitry **210** calculates the distance between the rover **110** and the satellite **125** using the amount of time it took to receive the signal. In some examples, the location calculation circuitry **210** determines the current location data based on the distance from the satellite **125**. In some examples, the location calculation circuitry **210** receives signals from a network of satellites that include the satellite **125**. In such examples, the location calculation circuitry **210** determines the current location data based on comparing the distances from the different satellites in the network. In some examples, the location calculation circuitry **210** receives location correction data from the example correction determination circuitry **225**, which is discussed in further detail below. In some examples, the location correction data includes calculated error value(s) for the satellite **125** and/or the network of satellites. The location calculation circuitry **210** adjusts the current location data with the received error value(s).

(23) In the illustrated example of FIG. 2, the example accuracy determination circuitry **215**

calculates the accuracy of the current location data. In some examples, the accuracy determination circuitry **215** determines an error metric for the current location data. In some examples, a standardized form of determining error can be used to determine the error metric such as, horizontal dilution of precision (HDOP), vertical dilution of precision (VDOP), etc. However, other forms of determining/calculating an error metric for current location data can be additionally and/or alternatively be used. In some examples, the accuracy of the current location data is based on the determined error metric. In some examples, the accuracy determination circuitry **215** calculates the accuracy of adjusted location data from the location calculation circuitry **210**. In some examples, the adjusted location data is the current location data adjusted with received error value(s) from the example correction determination circuitry **225**. The accuracy determination circuitry **215** determines if the accuracy satisfies a threshold. In some examples, the threshold is application specific (e.g., guidance vs elevation control). In some examples, the threshold is based on the type of field operation that is being done. For example, if the field operation for the device associated with the rover **110** is planting, the threshold may be set to a sub inch difference. In another example, if the field operation for the device is tillage, the threshold may be set to a ± 1 inch difference. However, the threshold may be set to any other value(s) for different field operations. In some examples, the threshold is user configurable (e.g., the user sets the threshold via a user interface). The accuracy determination circuitry **215** compares the error metric of the accuracy to the threshold. In some examples, the accuracy determination circuitry **215** determines that the accuracy does not satisfy the threshold when the error metric is below the threshold.

(24) The example correction request circuitry **220** connects to a correction stream based on the output from the accuracy determination circuitry **215**. If the example accuracy determination circuitry **215** determines that the accuracy does not satisfy the threshold, then the example correction request circuitry **220** connects to the correction stream. The example correction request circuitry **220** requests location correction data from the example base circuitry **122** through the correction stream. In some examples, the correction request circuitry **220** includes identification information for the location correction data in the request. In some examples, the identification information includes identifiers associated with a specific satellite (e.g., the satellite **125**). However, other identification information may be additionally and/or alternatively included in the request for correction data.

(25) In some examples, the correction request circuitry **220** includes the current location of the rover **110** in the request. For example, the correction request circuitry **220** can request location correction data from a virtual base station that includes correction data from a plurality of bases (e.g., the base **120** of FIG. **1**). The virtual base station can aggregate location correction data from neighboring bases included in the plurality of bases. In such examples, the correction request circuitry **220** includes the current location of the rover **110** in the request, and the virtual base station can provide the location correction data from the base(s) (e.g., the base **120**) that are near the current location of the rover **110**. If the example accuracy determination circuitry **215** determines that the accuracy does satisfy a threshold, then the example correction request circuitry **220** does not connect to the correction stream. In some examples, the correction request circuitry **220** is already connected to the correction stream based on a previous output from the accuracy determination circuitry **215**. In such examples, the correction request circuitry **220** determines if the correction request circuitry **220** is already connected to the correction stream. If the accuracy determination circuitry **215** determines that the accuracy does satisfy a threshold and the correction request circuitry **220** determines the correction request circuitry **220** is connected to the correction stream, then the correction request circuitry **220** stops the flow of location correction data (e.g., disconnects) from the correction stream. In some examples, the correction request circuitry **220** requests location correction data from the example base circuitry **122** through a subscription to a correction service. For example, the correction request circuitry **220** includes identification information for the location correction data in a request to the correction service. However, the

correction request circuitry **220** can request location correction data in additional and/or alternative ways.

(26) The example correction determination circuitry **225** receives location correction data from the example base circuitry **122** through the cell tower **115**. The correction determination circuitry **225** receives the error value(s) included in the location correction data for the satellite **125** and/or a network of satellites. In some examples, the correction determination circuitry **225** receives the location correction data through the correction stream. The correction determination circuitry **225** receives the location correction data when the correction request circuitry **220** is connected to the correction stream. In some examples, the correction determination circuitry **225** receives the location correction data through an SMS message. For example, if the correction request circuitry **220** requests the location correction data through a correction service, the correction service can provide the location correction data in an SMS message sent using the cell tower **115**. The correction determination circuitry **225** provides the location correction data to the example location calculation circuitry **210**.

(27) In the illustrated example of FIG. 2, the example location request circuitry **230** receives signals from the satellite **125** of FIG. 1. In some examples, the location request circuitry **230** receives signals from a plurality of satellites included in a network of satellites. The example location request circuitry **230** determines the location data for the base circuitry **122** using the received signals from the satellite **125**. The location request circuitry **230** determines the amount of time it took for the location request circuitry **230** to receive a signal from the satellite **125**. The location request circuitry **230** calculates the distance between the base circuitry **122** and the satellite **125** using the amount of time it took to receive the signal. In some examples, the location request circuitry **230** determines the location data of the base **120** based on the distance from the satellite **125**.

(28) The example error calculation circuitry **235** calculates an error value for the satellite **125**. The example error calculation circuitry **235** compares the location data determined by the location request circuitry **230** to the known location of the base **120**. The error calculation circuitry **235** calculates an error value based on the comparison of the location data from the location request circuitry **230** to the known location. In some examples, the error value is a percent difference calculation between the determined location data and the known location of the base **120**. However, other calculations for determining the error value may additionally and/or alternatively be used. The error calculation circuitry **235** stores the error value in the error database **240**. In some examples, the error calculation circuitry **235** calculates error values for a plurality of satellites in a network of satellites.

(29) The example error database **240** stores the error value for the satellite **125**. In some examples, the error database **240** stores error values for a plurality of satellites included in a network of satellites. The error database **240** is implemented by any memory, storage device, and/or storage disc for storing data such as, for example, flash memory, magnetic media, optical media, solid state memory, hard drive(s), thumb drive(s), etc. Furthermore, the data stored in the error database **240** may be in any data format such as, for example, binary data, comma delimited data, tab delimited data, structured query language (SQL) structures, etc.

(30) The example request receiver circuitry **245** determines whether the example base circuitry **122** receives a request for correction data. In some examples, the request receiver circuitry **245** receives the request for correction data from the example correction request circuitry **220**. In some examples, the request receiver circuitry **245** receives the request through the correction stream in the cellular network of the example cell tower **115**. In some examples, the request receiver circuitry **245** receives the request for correction data from a correction service. For example, if the correction request circuitry **220** requests the location correction data through a correction service, the request receiver circuitry **245** receives the request for correction data via the correction service. In some examples, the request receiver circuitry **245** determines the identification information of

the request for correction data. In some examples, the identification information includes identifiers associated with a specific satellite (e.g., the satellite **125**). However, other identification information may be additionally and/or alternatively included in the request for correction data. The request receiver circuitry **245** provides the identification information of the request to the example correction transmission circuitry **250**. In some examples, the request receiver circuitry **245** determines the current location of the rover **110** from the request for correction data. For example, request for correction data can include a request for location correction data from a virtual base station that includes correction data from a plurality of bases (e.g., the base **120** of FIG. **1**). In such examples, the request receiver circuitry **245** provides the request for correction data to the virtual base station, where the virtual base station can provide the location correction data from the base(s) (e.g., the base **120**) that are near the current location of the rover **110**.

(31) The example correction transmission circuitry **250** receives the request for correction data from the request receiver circuitry **245**. In some examples, the correction transmission circuitry **250** receives the identification information of the request for correction data. If the example request receiver circuitry **245** determines that the base circuitry **122** receives a request for correction data, then the correction transmission circuitry **250** identifies the requested error value(s) in the error database **240** associated with the identification information included in the request for correction data. The correction transmission circuitry **250** transmits the requested error value(s) from the error database **240** to the example correction determination circuitry **225**. In some examples, the correction transmission circuitry **250** transmits the requested error value(s) in a correction stream through the cellular network of the example cell tower **115**. In some examples, the correction transmission circuitry **250** transmits the requested error value(s) to the correction service, where the correction service provides the requested error value(s) in a short message service (SMS) message.

(32) In some examples, the rover circuitry **112** includes means for calculating location. For example, the means for calculating location may be implemented by the location calculation circuitry **210**. In some examples, the location calculation circuitry **210** may be instantiated by processor circuitry such as the example processor circuitry **512** of FIG. **5**. For instance, the location calculation circuitry **210** may be instantiated by the example microprocessor **700** of FIG. **7** executing machine executable instructions such as those implemented by at least blocks **305**, **335** of FIG. **3**. In some examples, the location calculation circuitry **210** may be instantiated by hardware logic circuitry, which may be implemented by an ASIC, XPU, or the FPGA circuitry **800** of FIG. **8** structured to perform operations corresponding to the machine readable instructions. Additionally or alternatively, the location calculation circuitry **210** may be instantiated by any other combination of hardware, software, and/or firmware. For example, the location calculation circuitry **210** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, an XPU, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to execute some or all of the machine readable instructions and/or to perform some or all of the operations corresponding to the machine readable instructions without executing software or firmware, but other structures are likewise appropriate.

(33) In some examples, the rover circuitry **112** includes means for determining accuracy. For example, the means for determining accuracy may be implemented by the accuracy determination circuitry **215**. In some examples, the accuracy determination circuitry **215** may be instantiated by processor circuitry such as the example processor circuitry **512** of FIG. **5**. For instance, the accuracy determination circuitry **215** may be instantiated by the example microprocessor **700** of FIG. **7** executing machine executable instructions such as those implemented by at least blocks **310**, **315** of FIG. **3**. In some examples, the accuracy determination circuitry **215** may be instantiated by hardware logic circuitry, which may be implemented by an ASIC, XPU, or the FPGA circuitry **800** of FIG. **8** structured to perform operations corresponding to the machine readable instructions. Additionally or alternatively, the accuracy determination circuitry **215** may be instantiated by any

other combination of hardware, software, and/or firmware. For example, the accuracy determination circuitry **215** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, an XPU, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to execute some or all of the machine readable instructions and/or to perform some or all of the operations corresponding to the machine readable instructions without executing software or firmware, but other structures are likewise appropriate.

(34) In some examples, the rover circuitry **112** includes means for requesting corrections. For example, the means for requesting corrections may be implemented by the correction request circuitry **220**. In some examples, the correction request circuitry **220** may be instantiated by processor circuitry such as the example processor circuitry **512** of FIG. 5. For instance, the correction request circuitry **220** may be instantiated by the example microprocessor **700** of FIG. 7 executing machine executable instructions such as those implemented by at least blocks **320**, **325**, **340**, **345** of FIG. 3. In some examples, the correction request circuitry **220** may be instantiated by hardware logic circuitry, which may be implemented by an ASIC, XPU, or the FPGA circuitry **800** of FIG. 8 structured to perform operations corresponding to the machine readable instructions. Additionally or alternatively, the correction request circuitry **220** may be instantiated by any other combination of hardware, software, and/or firmware. For example, the correction request circuitry **220** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, an XPU, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to execute some or all of the machine readable instructions and/or to perform some or all of the operations corresponding to the machine readable instructions without executing software or firmware, but other structures are likewise appropriate.

(35) In some examples, the rover circuitry **112** includes means for determining corrections. For example, the means for determining corrections may be implemented by the correction determination circuitry **225**. In some examples, the correction determination circuitry **225** may be instantiated by processor circuitry such as the example processor circuitry **512** of FIG. 5. For instance, the correction determination circuitry **225** may be instantiated by the example microprocessor **700** of FIG. 7 executing machine executable instructions such as those implemented by at least block **330** of FIG. 3. In some examples, the correction determination circuitry **225** may be instantiated by hardware logic circuitry, which may be implemented by an ASIC, XPU, or the FPGA circuitry **800** of FIG. 8 structured to perform operations corresponding to the machine readable instructions. Additionally or alternatively, the correction determination circuitry **225** may be instantiated by any other combination of hardware, software, and/or firmware. For example, the correction determination circuitry **225** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, an XPU, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to execute some or all of the machine readable instructions and/or to perform some or all of the operations corresponding to the machine readable instructions without executing software or firmware, but other structures are likewise appropriate.

(36) In some examples, the base circuitry **122** includes means for requesting location. For example, the means for requesting location may be implemented by the location request circuitry **230**. In some examples, the location request circuitry **230** may be instantiated by processor circuitry such as the example processor circuitry **612** of FIG. 6. For instance, the location request circuitry **230** may be instantiated by the example microprocessor **700** of FIG. 7 executing machine executable instructions such as those implemented by at least block **405** of FIG. 4. In some examples, the location request circuitry **230** may be instantiated by hardware logic circuitry, which may be implemented by an ASIC, XPU, or the FPGA circuitry **800** of FIG. 8 structured to perform operations corresponding to the machine readable instructions. Additionally or alternatively, the

location request circuitry **230** may be instantiated by any other combination of hardware, software, and/or firmware. For example, the location request circuitry **230** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, an XPU, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to execute some or all of the machine readable instructions and/or to perform some or all of the operations corresponding to the machine readable instructions without executing software or firmware, but other structures are likewise appropriate.

(37) In some examples, the base circuitry **122** includes means for calculating error. For example, the means for calculating error may be implemented by the error calculation circuitry **235**. In some examples, the error calculation circuitry **235** may be instantiated by processor circuitry such as the example processor circuitry **612** of FIG. **6**. For instance, the error calculation circuitry **235** may be instantiated by the example microprocessor **700** of FIG. **7** executing machine executable instructions such as those implemented by at least blocks **410**, **415**, **420** of FIG. **4**. In some examples, the error calculation circuitry **235** may be instantiated by hardware logic circuitry, which may be implemented by an ASIC, XPU, or the FPGA circuitry **800** of FIG. **8** structured to perform operations corresponding to the machine readable instructions. Additionally or alternatively, the error calculation circuitry **235** may be instantiated by any other combination of hardware, software, and/or firmware. For example, the error calculation circuitry **235** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, an XPU, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to execute some or all of the machine readable instructions and/or to perform some or all of the operations corresponding to the machine readable instructions without executing software or firmware, but other structures are likewise appropriate.

(38) In some examples, the base circuitry **122** includes means for receiving requests. For example, the means for receiving requests may be implemented by the request receiver circuitry **245**. In some examples, the request receiver circuitry **245** may be instantiated by processor circuitry such as the example processor circuitry **612** of FIG. **6**. For instance, the request receiver circuitry **245** may be instantiated by the example microprocessor **700** of FIG. **7** executing machine executable instructions such as those implemented by at least block **425** of FIG. **4**. In some examples, the request receiver circuitry **245** may be instantiated by hardware logic circuitry, which may be implemented by an ASIC, XPU, or the FPGA circuitry **800** of FIG. **8** structured to perform operations corresponding to the machine readable instructions. Additionally or alternatively, the request receiver circuitry **245** may be instantiated by any other combination of hardware, software, and/or firmware. For example, the request receiver circuitry **245** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, an XPU, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to execute some or all of the machine readable instructions and/or to perform some or all of the operations corresponding to the machine readable instructions without executing software or firmware, but other structures are likewise appropriate.

(39) In some examples, the base circuitry **122** includes means for transmitting corrections. For example, the means for transmitting corrections may be implemented by the correction transmission circuitry **250**. In some examples, the correction transmission circuitry **250** may be instantiated by processor circuitry such as the example processor circuitry **612** of FIG. **6**. For instance, the correction transmission circuitry **250** may be instantiated by the example microprocessor **700** of FIG. **7** executing machine executable instructions such as those implemented by at least block **430** of FIG. **4**. In some examples, the correction transmission circuitry **250** may be instantiated by hardware logic circuitry, which may be implemented by an ASIC, XPU, or the FPGA circuitry **800** of FIG. **8** structured to perform operations corresponding to the machine readable instructions. Additionally or alternatively, the correction transmission circuitry **250** may be instantiated by any other combination of hardware, software, and/or firmware.

For example, the correction transmission circuitry **250** may be implemented by at least one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, an XPU, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to execute some or all of the machine readable instructions and/or to perform some or all of the operations corresponding to the machine readable instructions without executing software or firmware, but other structures are likewise appropriate.

(40) While an example manner of implementing the rover circuitry **112** of FIG. **1** is illustrated in FIG. **2**, one or more of the elements, processes, and/or devices illustrated in FIG. **2** may be combined, divided, re-arranged, omitted, eliminated, and/or implemented in any other way. Further, the example location calculation circuitry **210**, the example accuracy determination circuitry **215**, the example correction request circuitry **220**, the example correction determination circuitry **225**, and/or, more generally, the example rover circuitry **112** of FIG. **1**, may be implemented by hardware alone or by hardware in combination with software and/or firmware. Thus, for example, any of the example location calculation circuitry **210**, the example accuracy determination circuitry **215**, the example correction request circuitry **220**, the example correction determination circuitry **225**, and/or, more generally, the example rover circuitry **112**, could be implemented by processor circuitry, analog circuit(s), digital circuit(s), logic circuit(s), programmable processor(s), programmable microcontroller(s), graphics processing unit(s) (GPU(s)), digital signal processor(s) (DSP(s)), application specific integrated circuit(s) (ASIC(s)), programmable logic device(s) (PLD(s)), and/or field programmable logic device(s) (FPLD(s)) such as Field Programmable Gate Arrays (FPGAs). Further still, the example rover circuitry **112** of FIG. **1** may include one or more elements, processes, and/or devices in addition to, or instead of, those illustrated in FIG. **2**, and/or may include more than one of any or all of the illustrated elements, processes and devices.

(41) A flowchart representative of example machine readable instructions, which may be executed to configure processor circuitry to implement the rover circuitry **112** of FIG. **2**, is shown in FIG. **3**. The machine readable instructions may be one or more executable programs or portion(s) of an executable program for execution by processor circuitry, such as the processor circuitry **512** shown in the example processor platform **500** discussed below in connection with FIG. **5** and/or the example processor circuitry discussed below in connection with FIGS. **7** and/or **8**. The program may be embodied in software stored on one or more non-transitory computer readable storage media such as a compact disk (CD), a floppy disk, a hard disk drive (HDD), a solid-state drive (SSD), a digital versatile disk (DVD), a Blu-ray disk, a volatile memory (e.g., Random Access Memory (RAM) of any type, etc.), or a non-volatile memory (e.g., electrically erasable programmable read-only memory (EEPROM), FLASH memory, an HDD, an SSD, etc.) associated with processor circuitry located in one or more hardware devices, but the entire program and/or parts thereof could alternatively be executed by one or more hardware devices other than the processor circuitry and/or embodied in firmware or dedicated hardware. The machine readable instructions may be distributed across multiple hardware devices and/or executed by two or more hardware devices (e.g., a server and a client hardware device). For example, the client hardware device may be implemented by an endpoint client hardware device (e.g., a hardware device associated with a user) or an intermediate client hardware device (e.g., a radio access network (RAN)) gateway that may facilitate communication between a server and an endpoint client hardware device). Similarly, the non-transitory computer readable storage media may include one or more mediums located in one or more hardware devices. Further, although the example program is described with reference to the flowchart illustrated in FIG. **3**, many other methods of implementing the example rover circuitry **112** may alternatively be used. For example, the order of execution of the blocks may be changed, and/or some of the blocks described may be changed, eliminated, or combined. Additionally or alternatively, any or all of the blocks may be implemented by one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, a comparator, an operational-amplifier (op-amp), a logic

circuit, etc.) structured to perform the corresponding operation without executing software or firmware. The processor circuitry may be distributed in different network locations and/or local to one or more hardware devices (e.g., a single-core processor (e.g., a single core central processor unit (CPU)), a multi-core processor (e.g., a multi-core CPU, an XPU, etc.) in a single machine, multiple processors distributed across multiple servers of a server rack, multiple processors distributed across one or more server racks, a CPU and/or a FPGA located in the same package (e.g., the same integrated circuit (IC) package or in two or more separate housings, etc.).

(42) While an example manner of implementing the base circuitry **122** of FIG. **1** is illustrated in FIG. **2**, one or more of the elements, processes, and/or devices illustrated in FIG. **2** may be combined, divided, re-arranged, omitted, eliminated, and/or implemented in any other way. Further, the example location request circuitry **230**, the example error calculation circuitry **235**, the example error database **240**, the example request receiver circuitry **245**, the example correction transmission circuitry **250**, and/or, more generally, the example base circuitry **122** of FIG. **1**, may be implemented by hardware alone or by hardware in combination with software and/or firmware. Thus, for example, any of the example the example location request circuitry **230**, the example error calculation circuitry **235**, the example error database **240**, the example request receiver circuitry **245**, the example correction transmission circuitry **250**, and/or, more generally, the example base circuitry **122**, could be implemented by processor circuitry, analog circuit(s), digital circuit(s), logic circuit(s), programmable processor(s), programmable microcontroller(s), graphics processing unit(s) (GPU(s)), digital signal processor(s) (DSP(s)), application specific integrated circuit(s) (ASIC(s)), programmable logic device(s) (PLD(s)), and/or field programmable logic device(s) (FPLD(s)) such as Field Programmable Gate Arrays (FPGAs). Further still, the example base circuitry **122** of FIG. **1** may include one or more elements, processes, and/or devices in addition to, or instead of, those illustrated in FIG. **2**, and/or may include more than one of any or all of the illustrated elements, processes and devices.

(43) A flowchart representative of example machine readable instructions, which may be executed to configure processor circuitry to implement the base circuitry **122** of FIG. **2**, is shown in FIG. **4**. The machine readable instructions may be one or more executable programs or portion(s) of an executable program for execution by processor circuitry, such as the processor circuitry **612** shown in the example processor platform **600** discussed below in connection with FIG. **6** and/or the example processor circuitry discussed below in connection with FIGS. **7** and/or **8**. The program may be embodied in software stored on one or more non-transitory computer readable storage media such as a compact disk (CD), a floppy disk, a hard disk drive (HDD), a solid-state drive (SSD), a digital versatile disk (DVD), a Blu-ray disk, a volatile memory (e.g., Random Access Memory (RAM) of any type, etc.), or a non-volatile memory (e.g., electrically erasable programmable read-only memory (EEPROM), FLASH memory, an HDD, an SSD, etc.) associated with processor circuitry located in one or more hardware devices, but the entire program and/or parts thereof could alternatively be executed by one or more hardware devices other than the processor circuitry and/or embodied in firmware or dedicated hardware. The machine readable instructions may be distributed across multiple hardware devices and/or executed by two or more hardware devices (e.g., a server and a client hardware device). For example, the client hardware device may be implemented by an endpoint client hardware device (e.g., a hardware device associated with a user) or an intermediate client hardware device (e.g., a radio access network (RAN)) gateway that may facilitate communication between a server and an endpoint client hardware device). Similarly, the non-transitory computer readable storage media may include one or more mediums located in one or more hardware devices. Further, although the example program is described with reference to the flowchart illustrated in FIG. **4**, many other methods of implementing the example base circuitry **122** may alternatively be used. For example, the order of execution of the blocks may be changed, and/or some of the blocks described may be changed, eliminated, or combined. Additionally or alternatively, any or all of the blocks may be implemented

by one or more hardware circuits (e.g., processor circuitry, discrete and/or integrated analog and/or digital circuitry, an FPGA, an ASIC, a comparator, an operational-amplifier (op-amp), a logic circuit, etc.) structured to perform the corresponding operation without executing software or firmware. The processor circuitry may be distributed in different network locations and/or local to one or more hardware devices (e.g., a single-core processor (e.g., a single core central processor unit (CPU)), a multi-core processor (e.g., a multi-core CPU, an XPU, etc.) in a single machine, multiple processors distributed across multiple servers of a server rack, multiple processors distributed across one or more server racks, a CPU and/or a FPGA located in the same package (e.g., the same integrated circuit (IC) package or in two or more separate housings, etc.).

(44) The machine readable instructions described herein may be stored in one or more of a compressed format, an encrypted format, a fragmented format, a compiled format, an executable format, a packaged format, etc. Machine readable instructions as described herein may be stored as data or a data structure (e.g., as portions of instructions, code, representations of code, etc.) that may be utilized to create, manufacture, and/or produce machine executable instructions. For example, the machine readable instructions may be fragmented and stored on one or more storage devices and/or computing devices (e.g., servers) located at the same or different locations of a network or collection of networks (e.g., in the cloud, in edge devices, etc.). The machine readable instructions may require one or more of installation, modification, adaptation, updating, combining, supplementing, configuring, decryption, decompression, unpacking, distribution, reassignment, compilation, etc., in order to make them directly readable, interpretable, and/or executable by a computing device and/or other machine. For example, the machine readable instructions may be stored in multiple parts, which are individually compressed, encrypted, and/or stored on separate computing devices, wherein the parts when decrypted, decompressed, and/or combined form a set of machine executable instructions that implement one or more operations that may together form a program such as that described herein.

(45) In another example, the machine readable instructions may be stored in a state in which they may be read by processor circuitry, but require addition of a library (e.g., a dynamic link library (DLL)), a software development kit (SDK), an application programming interface (API), etc., in order to execute the machine readable instructions on a particular computing device or other device. In another example, the machine readable instructions may need to be configured (e.g., settings stored, data input, network addresses recorded, etc.) before the machine readable instructions and/or the corresponding program(s) can be executed in whole or in part. Thus, machine readable media, as used herein, may include machine readable instructions and/or program(s) regardless of the particular format or state of the machine readable instructions and/or program(s) when stored or otherwise at rest or in transit.

(46) The machine readable instructions described herein can be represented by any past, present, or future instruction language, scripting language, programming language, etc. For example, the machine readable instructions may be represented using any of the following languages: C, C++, Java, C #, Perl, Python, JavaScript, HyperText Markup Language (HTML), Structured Query Language (SQL), Swift, etc.

(47) As mentioned above, the example operations of FIGS. 3 and/or 4 may be implemented using executable instructions (e.g., computer and/or machine readable instructions) stored on one or more non-transitory computer and/or machine readable media such as optical storage devices, magnetic storage devices, an HDD, a flash memory, a read-only memory (ROM), a CD, a DVD, a cache, a RAM of any type, a register, and/or any other storage device or storage disk in which information is stored for any duration (e.g., for extended time periods, permanently, for brief instances, for temporarily buffering, and/or for caching of the information). As used herein, the terms non-transitory computer readable medium, non-transitory computer readable storage medium, non-transitory machine readable medium, and non-transitory machine readable storage medium are expressly defined to include any type of computer readable storage device and/or storage disk and

to exclude propagating signals and to exclude transmission media. As used herein, the terms “computer readable storage device” and “machine readable storage device” are defined to include any physical (mechanical and/or electrical) structure to store information, but to exclude propagating signals and to exclude transmission media. Examples of computer readable storage devices and machine readable storage devices include random access memory of any type, read only memory of any type, solid state memory, flash memory, optical discs, magnetic disks, disk drives, and/or redundant array of independent disks (RAID) systems. As used herein, the term “device” refers to physical structure such as mechanical and/or electrical equipment, hardware, and/or circuitry that may or may not be configured by computer readable instructions, machine readable instructions, etc., and/or manufactured to execute computer readable instructions, machine readable instructions, etc.

(48) “Including” and “comprising” (and all forms and tenses thereof) are used herein to be open ended terms. Thus, whenever a claim employs any form of “include” or “comprise” (e.g., comprises, includes, comprising, including, having, etc.) as a preamble or within a claim recitation of any kind, it is to be understood that additional elements, terms, etc., may be present without falling outside the scope of the corresponding claim or recitation. As used herein, when the phrase “at least” is used as the transition term in, for example, a preamble of a claim, it is open-ended in the same manner as the term “comprising” and “including” are open ended. The term “and/or” when used, for example, in a form such as A, B, and/or C refers to any combination or subset of A, B, C such as (1) A alone, (2) B alone, (3) C alone, (4) A with B, (5) A with C, (6) B with C, or (7) A with B and with C. As used herein in the context of describing structures, components, items, objects and/or things, the phrase “at least one of A and B” is intended to refer to implementations including any of (1) at least one A, (2) at least one B, or (3) at least one A and at least one B. Similarly, as used herein in the context of describing structures, components, items, objects and/or things, the phrase “at least one of A or B” is intended to refer to implementations including any of (1) at least one A, (2) at least one B, or (3) at least one A and at least one B. As used herein in the context of describing the performance or execution of processes, instructions, actions, activities and/or steps, the phrase “at least one of A and B” is intended to refer to implementations including any of (1) at least one A, (2) at least one B, or (3) at least one A and at least one B. Similarly, as used herein in the context of describing the performance or execution of processes, instructions, actions, activities and/or steps, the phrase “at least one of A or B” is intended to refer to implementations including any of (1) at least one A, (2) at least one B, or (3) at least one A and at least one B.

(49) As used herein, singular references (e.g., “a”, “an”, “first”, “second”, etc.) do not exclude a plurality. The term “a” or “an” object, as used herein, refers to one or more of that object. The terms “a” (or “an”), “one or more”, and “at least one” are used interchangeably herein. Furthermore, although individually listed, a plurality of means, elements or method actions may be implemented by, e.g., the same entity or object. Additionally, although individual features may be included in different examples or claims, these may possibly be combined, and the inclusion in different examples or claims does not imply that a combination of features is not feasible and/or advantageous.

(50) FIG. 3 is a flowchart representative of example machine readable instructions and/or example operations **300** that may be executed and/or instantiated by processor circuitry to implement the example rover circuitry **112** of FIGS. 1 and/or 2. The machine readable instructions and/or the operations **300** of FIG. 3 begin at block **305**, at which the example location calculation circuitry **210** of FIG. 2 determines the current location data for the example rover **110** of FIG. 1. In some examples, the location calculation circuitry **210** receives signals from the satellite **125**. The location calculation circuitry **210** determines the amount of time it took for the location calculation circuitry **210** to receive the signal from the satellite **125**. The location calculation circuitry **210** calculates the distance between the rover **110** and the satellite **125** using the amount of time it took to receive the

signal. In some examples, the location calculation circuitry **210** determines the current location data based on the distance from the satellite **125**. In some examples, the location calculation circuitry **210** receives signals from a network of satellites that include the satellite **125**. In such examples, the location calculation circuitry **210** determines the current location data based on comparing the distances from the different satellites in the network.

(51) At block **310**, the example accuracy determination circuitry **215** of FIG. 2 calculates the accuracy of current location data. In some examples, the accuracy determination circuitry **215** determines an error metric for the current location data. In some examples, the accuracy of the current location data is based on the determined error metric. In some examples, the error metric can include a distance measurement between the current location data and the actual location of the rover circuitry **112**, a percent difference between the current location data and the actual location of the rover circuitry **112**, etc. In some examples, the accuracy determination circuitry **215** calculates the accuracy of adjusted location data from the location calculation circuitry **210**. In some examples, the adjusted location data is the current location data adjusted with received error value(s) from the example correction determination circuitry **225**.

(52) At block **315**, the example accuracy determination circuitry **215** of FIG. 2 determines if the accuracy satisfies a threshold. In some examples, the threshold is application specific (e.g., guidance v. elevation control). In some examples, the threshold is based on the type of field operation that is being performed. For example, if the field operation for the device associated with the rover is planting, the threshold may be set to a sub inch difference, and if the field operation for the device is tillage, the threshold may be set to a ± 1 inch difference. However, the threshold may be set to any other value for different field operations. In some examples, the threshold is user configurable (e.g., the user sets the threshold via a user interface). The accuracy determination circuitry **215** compares the error metric of the accuracy to the threshold. If the example accuracy determination circuitry **215** determines that the accuracy does not satisfy the threshold, then the operations **300** continue to block **320** at which the example correction request circuitry **220** connects to a correction stream. If the example accuracy determination circuitry **215** determines that the accuracy does satisfy a threshold, then the operations **300** continue to block **340** at which the example correction request circuitry **220** determines if the example correction request circuitry **220** is connected to the correction stream.

(53) At block **320**, the example correction request circuitry **220** of FIG. 2 connects to a correction stream. In some examples, the correction request circuitry **220** connects to the correction stream through the cellular network of the example cell tower **115**.

(54) At block **325**, the example correction request circuitry **220** requests correction data. The example correction request circuitry **220** requests location correction data from the example base circuitry **122** through the correction stream. In some examples, the correction request circuitry **220** includes identification information for the location correction data in the request. In some examples, the identification information includes identifiers associated with a specific satellite (e.g., the satellite **125**). However, other identification information may be additionally and/or alternatively included in the request for correction data. In some examples, the correction request circuitry **220** includes the current location of the rover circuitry **112** in the request. For example, the correction request circuitry **220** can request location correction data from a virtual base station that includes correction data from a plurality of bases (e.g., base circuitry **122**). The virtual base station can aggregate location correction data from neighboring bases included in the plurality of bases. In such examples, the correction request circuitry **220** includes the current location of the rover circuitry **112** in the request, and the virtual base station can provide the location correction data from the base(s) (e.g., base circuitry **122**) that are near the current location of the rover circuitry **112**. In some examples, the correction request circuitry **220** requests location correction data from the example base circuitry **122** through a subscription to a correction service. For example, the correction request circuitry **220** includes identification information for the location correction data

in a request to the correction service. However, the correction request circuitry **220** can request location correction data in additional and/or alternative ways.

(55) At block **330**, the example correction determination circuitry **225** of FIG. 2 receives an error value of the location correction data. The correction determination circuitry **225** receives location correction data from the correction transmission circuitry **250** of the base circuitry **122**. The correction determination circuitry **225** receives the error value included in the location correction data for the satellite **125**. In some examples, the correction determination circuitry **225** receives the location correction data through the correction stream. In some examples, the correction determination circuitry **225** receives location correction data from a virtual base station that includes correction data from the base circuitry **122** (e.g., from the correction transmission circuitry **250**). In some examples, the correction determination circuitry **225** receives the location correction data through an SMS message. For example, if the correction request circuitry **220** requests the location correction data through a correction service, the correction service can provide the location correction data in an SMS message sent using the cell tower **115**. The correction determination circuitry **225** provides the location correction data to the example location calculation circuitry **210**.

(56) At block **335**, the example location calculation circuitry **210** of FIG. 2 adjusts the current location data with the received error value for the example satellite **125**. The location calculation circuitry **210** adjusts the current location data with the received error value. Once the location calculation circuitry **210** adjusted the current location data with the received error value, the example operations **300** return to block **310** at which the example accuracy determination circuitry **215** calculates the accuracy of the adjusted current location data.

(57) At block **340**, the example correction request circuitry **220** of FIG. 2 determines if the correction request circuitry **220** is connected to the correction stream. In some examples, the correction request circuitry **220** is already connected to the correction stream based on a previous output from the accuracy determination circuitry **215**. In such examples, the correction request circuitry **220** determines if the correction request circuitry **220** is already connected to the correction stream. If the example correction request circuitry **220** determines that the correction request circuitry **220** is connected to the correction stream, then process **300** continues to block **345** at which the correction request circuitry **220** disconnects from the correction stream. If the example correction request circuitry **220** determines that the correction request circuitry **220** is not connected to the correction stream, then the operations **300** end.

(58) At block **345**, the example correction request circuitry **220** of FIG. 2 disconnects from the correction stream. In some examples, the correction request circuitry **220** keeps the connection to the correction stream but stops the flow of location correction data from the correction stream. Once the correction request circuitry **220** disconnects from the correction stream, the operations **300** end.

(59) FIG. 4 is a flowchart representative of example machine readable instructions and/or example operations **400** that may be executed and/or instantiated by processor circuitry to implement the example base circuitry **122** of FIGS. 1 and/or 2. The machine readable instructions and/or the operations **400** of FIG. 4 begin at block **405**, at which the example location request circuitry **230** of FIG. 2 determines the location data from the satellite **125** of FIG. 1. In some examples, the location request circuitry **230** receives signals from the satellite **125** of FIG. 1. In some examples, the location request circuitry **230** receives signals from a plurality of satellites included in a network of satellites. The example location request circuitry **230** determines the location data for the base circuitry **122** using the received signals from the satellite **125**. The location request circuitry **230** determines the amount of time it took for the location request circuitry **230** to receive a signal from the satellite **125**. The location request circuitry **230** calculates the distance between the base **120** of FIG. 1 and the satellite **125** using the amount of time it took to receive the signal. In some examples, the location request circuitry **230** determines the location data of the base **120** based on the distance from the satellite **125**.

(60) At block **410**, the example error calculation circuitry **235** of FIG. **2** compares the location data to a known location. The example error calculation circuitry **235** compares the location data determined by the location request circuitry **230** to the known location of the base **120**.

(61) At block **415**, the example error calculation circuitry **235** of FIG. **2** calculates an error value for the satellite **125**. The error calculation circuitry **235** calculates the error value based on the comparison of the location data from the location request circuitry **230** to the known location. In some examples, the error value is percent difference calculation between the determined location data and the known location of the base **120**. However, other calculations for determining the error value may additionally and/or alternatively be used.

(62) At block **420**, the example error calculation circuitry **235** of FIG. **2** stores the error value in the error database **240**.

(63) At block **425**, the example request receiver circuitry **245** of FIG. **2** determines whether the example base circuitry **122** receives a request for correction data. In some examples, the request receiver circuitry **245** receives the request for correction data from the example correction request circuitry **220**. In some examples, the request receiver circuitry **245** receives the request through the correction stream in the cellular network of the example cell tower **115**. In some examples, the request receiver circuitry **245** receives the request for correction data from a correction service. For example, if the correction request circuitry **220** requests the location correction data through a correction service, the request receiver circuitry **245** receives the request for correction data via the correction service. In some examples, the request receiver circuitry **245** determines the identification information of the request for correction data. In some examples, the identification information includes identifiers associated with a specific satellite (e.g., the satellite **125**). However, other identification information may be additionally and/or alternatively included in the request for correction data. In some examples, the request receiver circuitry **245** determines the current location of the rover circuitry **112** from the request for correction data. For example, request for correction data can include a request for location correction data from a virtual base station that includes correction data from a plurality of bases (e.g., the base **120**). In such examples, the request receiver circuitry **245** provides the request for correction data to the virtual base station, where the virtual base station can provide the location correction data from the base(s) (e.g., the base **120**) that are near the current location of the rover **110**. If the example request receiver circuitry **245** determines that the base circuitry **122** receives a request for correction data, then the operations **400** continue to block **430** at which the correction transmission circuitry **250** of FIG. **2** transmits the requested error value in the error database **240**. If the example request receiver circuitry **245** determines that the base circuitry **122** did not receive a request for correction data, then the operations **400** sit idle until the example location request circuitry **230** of FIG. **2** receives location data from the satellite **125**.

(64) At block **430**, the example correction transmission circuitry **250** of FIG. **2** transmits a requested error value in the error database **240**. The correction transmission circuitry **250** receives the request for correction data from the request receiver circuitry **245**. In some examples, the correction transmission circuitry **250** receives the identification information of the request for correction data. If the example request receiver circuitry **245** determines that the base circuitry **122** receives a request for correction data, then the correction transmission circuitry **250** identifies the requested error value(s) in the error database **240** associated with the identification information included in the request for correction data. The correction transmission circuitry **250** transmits the requested error value(s) from the error database **240** to the example correction determination circuitry **225**. In some examples, the correction transmission circuitry **250** transmits the requested error value(s) in a correction stream through the cellular network of the example cell tower **115**. In some examples, the correction transmission circuitry **250** transmits the requested error value(s) to a correction service, where the correction service provides the requested error value(s) in a short message service (SMS) message to the rover circuitry **112**. Once the example correction

transmission circuitry **250** transmits the requested error value, the operations **400** end.

(65) FIG. **5** is a block diagram of an example processor platform **500** structured to execute and/or instantiate the machine readable instructions and/or the operations of FIG. **3** to implement the rover circuitry **112** of FIG. **2**. The processor platform **500** can be, for example, a server, a personal computer, a workstation, a self-learning machine (e.g., a neural network), a mobile device (e.g., a cell phone, a smart phone, a tablet such as an iPad™), a personal digital assistant (PDA), an Internet appliance, a DVD player, a CD player, a digital video recorder, a Blu-ray player, a gaming console, a personal video recorder, a set top box, a headset (e.g., an augmented reality (AR) headset, a virtual reality (VR) headset, etc.) or other wearable device, or any other type of computing device.

(66) The processor platform **500** of the illustrated example includes processor circuitry **512**. The processor circuitry **512** of the illustrated example is hardware. For example, the processor circuitry **512** can be implemented by one or more integrated circuits, logic circuits, FPGAs, microprocessors, CPUs, GPUs, DSPs, and/or microcontrollers from any desired family or manufacturer. The processor circuitry **512** may be implemented by one or more semiconductor based (e.g., silicon based) devices. In this example, the processor circuitry **512** implements the example location calculation circuitry **210**, the example accuracy determination circuitry **215**, the example correction request circuitry **220**, and the example correction determination circuitry **225**.

(67) The processor circuitry **512** of the illustrated example includes a local memory **513** (e.g., a cache, registers, etc.). The processor circuitry **512** of the illustrated example is in communication with a main memory including a volatile memory **514** and a non-volatile memory **516** by a bus **518**. The volatile memory **514** may be implemented by Synchronous Dynamic Random Access Memory (SDRAM), Dynamic Random Access Memory (DRAM), RAMBUS® Dynamic Random Access Memory (RDRAM®), and/or any other type of RAM device. The non-volatile memory **516** may be implemented by flash memory and/or any other desired type of memory device. Access to the main memory **514**, **516** of the illustrated example is controlled by a memory controller **517**.

(68) The processor platform **500** of the illustrated example also includes interface circuitry **520**. The interface circuitry **520** may be implemented by hardware in accordance with any type of interface standard, such as an Ethernet interface, a universal serial bus (USB) interface, a Bluetooth® interface, a near field communication (NFC) interface, a Peripheral Component Interconnect (PCI) interface, and/or a Peripheral Component Interconnect Express (PCIe) interface.

(69) In the illustrated example, one or more input devices **522** are connected to the interface circuitry **520**. The input device(s) **522** permit(s) a user to enter data and/or commands into the processor circuitry **512**. The input device(s) **522** can be implemented by, for example, an audio sensor, a microphone, a camera (still or video), a keyboard, a button, a mouse, a touchscreen, a track-pad, a trackball, an isopoint device, and/or a voice recognition system.

(70) One or more output devices **524** are also connected to the interface circuitry **520** of the illustrated example. The output device(s) **524** can be implemented, for example, by display devices (e.g., a light emitting diode (LED), an organic light emitting diode (OLED), a liquid crystal display (LCD), a cathode ray tube (CRT) display, an in-place switching (IPS) display, a touchscreen, etc.), a tactile output device, a printer, and/or speaker. The interface circuitry **520** of the illustrated example, thus, typically includes a graphics driver card, a graphics driver chip, and/or graphics processor circuitry such as a GPU.

(71) The interface circuitry **520** of the illustrated example also includes a communication device such as a transmitter, a receiver, a transceiver, a modem, a residential gateway, a wireless access point, and/or a network interface to facilitate exchange of data with external machines (e.g., computing devices of any kind) by a network **526**. The communication can be by, for example, an Ethernet connection, a digital subscriber line (DSL) connection, a telephone line connection, a coaxial cable system, a satellite system, a line-of-site wireless system, a cellular telephone system, an optical connection, etc.

(72) The processor platform **500** of the illustrated example also includes one or more mass storage devices **528** to store software and/or data. Examples of such mass storage devices **528** include magnetic storage devices, optical storage devices, floppy disk drives, HDDs, CDs, Blu-ray disk drives, redundant array of independent disks (RAID) systems, solid state storage devices such as flash memory devices and/or SSDs, and DVD drives.

(73) The machine readable instructions **532**, which may be implemented by the machine readable instructions of FIG. **3**, may be stored in the mass storage device **528**, in the volatile memory **514**, in the non-volatile memory **516**, and/or on a removable non-transitory computer readable storage medium such as a CD or DVD.

(74) FIG. **6** is a block diagram of an example processor platform **600** structured to execute and/or instantiate the machine readable instructions and/or the operations of FIG. **4** to implement the base circuitry **122** of FIG. **2**. The processor platform **600** can be, for example, a server, a personal computer, a workstation, a self-learning machine (e.g., a neural network), a mobile device (e.g., a cell phone, a smart phone, a tablet such as an iPad™), a personal digital assistant (PDA), an Internet appliance, a DVD player, a CD player, a digital video recorder, a Blu-ray player, a gaming console, a personal video recorder, a set top box, a headset (e.g., an augmented reality (AR) headset, a virtual reality (VR) headset, etc.) or other wearable device, or any other type of computing device.

(75) The processor platform **600** of the illustrated example includes processor circuitry **612**. The processor circuitry **612** of the illustrated example is hardware. For example, the processor circuitry **612** can be implemented by one or more integrated circuits, logic circuits, FPGAs, microprocessors, CPUs, GPUs, DSPs, and/or microcontrollers from any desired family or manufacturer. The processor circuitry **612** may be implemented by one or more semiconductor based (e.g., silicon based) devices. In this example, the processor circuitry **612** implements the example location request circuitry **230**, the example error calculation circuitry **235**, the example error database **240**, the example request receiver circuitry **245**, and the example correction transmission circuitry **250**.

(76) The processor circuitry **612** of the illustrated example includes a local memory **613** (e.g., a cache, registers, etc.). The processor circuitry **612** of the illustrated example is in communication with a main memory including a volatile memory **614** and a non-volatile memory **616** by a bus **618**. The volatile memory **614** may be implemented by Synchronous Dynamic Random Access Memory (SDRAM), Dynamic Random Access Memory (DRAM), RAMBUS® Dynamic Random Access Memory (RDRAM®), and/or any other type of RAM device. The non-volatile memory **616** may be implemented by flash memory and/or any other desired type of memory device. Access to the main memory **614**, **616** of the illustrated example is controlled by a memory controller **617**.

(77) The processor platform **600** of the illustrated example also includes interface circuitry **620**. The interface circuitry **620** may be implemented by hardware in accordance with any type of interface standard, such as an Ethernet interface, a universal serial bus (USB) interface, a Bluetooth® interface, a near field communication (NFC) interface, a Peripheral Component Interconnect (PCI) interface, and/or a Peripheral Component Interconnect Express (PCIe) interface.

(78) In the illustrated example, one or more input devices **622** are connected to the interface circuitry **620**. The input device(s) **622** permit(s) a user to enter data and/or commands into the processor circuitry **612**. The input device(s) **622** can be implemented by, for example, an audio sensor, a microphone, a camera (still or video), a keyboard, a button, a mouse, a touchscreen, a track-pad, a trackball, an isopoint device, and/or a voice recognition system.

(79) One or more output devices **624** are also connected to the interface circuitry **620** of the illustrated example. The output device(s) **624** can be implemented, for example, by display devices (e.g., a light emitting diode (LED), an organic light emitting diode (OLED), a liquid crystal display (LCD), a cathode ray tube (CRT) display, an in-place switching (IPS) display, a touchscreen, etc.), a tactile output device, a printer, and/or speaker. The interface circuitry **620** of the illustrated

example, thus, typically includes a graphics driver card, a graphics driver chip, and/or graphics processor circuitry such as a GPU.

(80) The interface circuitry **620** of the illustrated example also includes a communication device such as a transmitter, a receiver, a transceiver, a modem, a residential gateway, a wireless access point, and/or a network interface to facilitate exchange of data with external machines (e.g., computing devices of any kind) by a network **626**. The communication can be by, for example, an Ethernet connection, a digital subscriber line (DSL) connection, a telephone line connection, a coaxial cable system, a satellite system, a line-of-site wireless system, a cellular telephone system, an optical connection, etc.

(81) The processor platform **600** of the illustrated example also includes one or more mass storage devices **628** to store software and/or data. Examples of such mass storage devices **628** include magnetic storage devices, optical storage devices, floppy disk drives, HDDs, CDs, Blu-ray disk drives, redundant array of independent disks (RAID) systems, solid state storage devices such as flash memory devices and/or SSDs, and DVD drives.

(82) The machine readable instructions **632**, which may be implemented by the machine readable instructions of FIG. 4, may be stored in the mass storage device **628**, in the volatile memory **614**, in the non-volatile memory **616**, and/or on a removable non-transitory computer readable storage medium such as a CD or DVD.

(83) FIG. 7 is a block diagram of an example implementation of the processor circuitry **512** of FIG. 5 and/or the processor circuitry **612** of FIG. 6. In this example, the processor circuitry **512** of FIG. 5 and/or the processor circuitry **612** of FIG. 6 is implemented by a microprocessor **700**. For example, the microprocessor **700** may be a general purpose microprocessor (e.g., general purpose microprocessor circuitry). The microprocessor **700** executes some or all of the machine readable instructions of the flowcharts of FIGS. 3 and/or 4 to effectively instantiate the rover circuitry **112** and/or the base circuitry **122** of FIG. 2 as logic circuits to perform the operations corresponding to those machine readable instructions. In some such examples, the rover circuitry **112** and/or the base circuitry **122** of FIG. 2 is instantiated by the hardware circuits of the microprocessor **700** in combination with the instructions. For example, the microprocessor **700** may be implemented by multi-core hardware circuitry such as a CPU, a DSP, a GPU, an XPU, etc. Although it may include any number of example cores **702** (e.g., 1 core), the microprocessor **700** of this example is a multi-core semiconductor device including N cores. The cores **702** of the microprocessor **700** may operate independently or may cooperate to execute machine readable instructions. For example, machine code corresponding to a firmware program, an embedded software program, or a software program may be executed by one of the cores **702** or may be executed by multiple ones of the cores **702** at the same or different times. In some examples, the machine code corresponding to the firmware program, the embedded software program, or the software program is split into threads and executed in parallel by two or more of the cores **702**. The software program may correspond to a portion or all of the machine readable instructions and/or operations represented by the flowcharts of FIGS. 3 and/or 4.

(84) The cores **702** may communicate by a first example bus **704**. In some examples, the first bus **704** may be implemented by a communication bus to effectuate communication associated with one(s) of the cores **702**. For example, the first bus **704** may be implemented by at least one of an Inter-Integrated Circuit (I2C) bus, a Serial Peripheral Interface (SPI) bus, a PCI bus, or a PCIe bus. Additionally or alternatively, the first bus **704** may be implemented by any other type of computing or electrical bus. The cores **702** may obtain data, instructions, and/or signals from one or more external devices by example interface circuitry **706**. The cores **702** may output data, instructions, and/or signals to the one or more external devices by the interface circuitry **706**. Although the cores **702** of this example include example local memory **720** (e.g., Level 1 (L1) cache that may be split into an L1 data cache and an L1 instruction cache), the microprocessor **700** also includes example shared memory **710** that may be shared by the cores (e.g., Level 2 (L2 cache)) for high-speed

access to data and/or instructions. Data and/or instructions may be transferred (e.g., shared) by writing to and/or reading from the shared memory **710**. The local memory **720** of each of the cores **702** and the shared memory **710** may be part of a hierarchy of storage devices including multiple levels of cache memory and the main memory (e.g., the main memory **514**, **516** of FIG. 5 and/or the main memory **614**, **616** of FIG. 6). Typically, higher levels of memory in the hierarchy exhibit lower access time and have smaller storage capacity than lower levels of memory. Changes in the various levels of the cache hierarchy are managed (e.g., coordinated) by a cache coherency policy.

(85) Each core **702** may be referred to as a CPU, DSP, GPU, etc., or any other type of hardware circuitry. Each core **702** includes control unit circuitry **714**, arithmetic and logic (AL) circuitry (sometimes referred to as an ALU) **716**, a plurality of registers **718**, the local memory **720**, and a second example bus **722**. Other structures may be present. For example, each core **702** may include vector unit circuitry, single instruction multiple data (SIMD) unit circuitry, load/store unit (LSU) circuitry, branch/jump unit circuitry, floating-point unit (FPU) circuitry, etc. The control unit circuitry **714** includes semiconductor-based circuits structured to control (e.g., coordinate) data movement within the corresponding core **702**. The AL circuitry **716** includes semiconductor-based circuits structured to perform one or more mathematic and/or logic operations on the data within the corresponding core **702**. The AL circuitry **716** of some examples performs integer based operations. In other examples, the AL circuitry **716** also performs floating point operations. In yet other examples, the AL circuitry **716** may include first AL circuitry that performs integer based operations and second AL circuitry that performs floating point operations. In some examples, the AL circuitry **716** may be referred to as an Arithmetic Logic Unit (ALU). The registers **718** are semiconductor-based structures to store data and/or instructions such as results of one or more of the operations performed by the AL circuitry **716** of the corresponding core **702**. For example, the registers **718** may include vector register(s), SIMD register(s), general purpose register(s), flag register(s), segment register(s), machine specific register(s), instruction pointer register(s), control register(s), debug register(s), memory management register(s), machine check register(s), etc. The registers **718** may be arranged in a bank as shown in FIG. 5. Alternatively, the registers **718** may be organized in any other arrangement, format, or structure including distributed throughout the core **702** to shorten access time. The second bus **722** may be implemented by at least one of an I2C bus, a SPI bus, a PCI bus, or a PCIe bus

(86) Each core **702** and/or, more generally, the microprocessor **700** may include additional and/or alternate structures to those shown and described above. For example, one or more clock circuits, one or more power supplies, one or more power gates, one or more cache home agents (CHAs), one or more converged/common mesh stops (CMSs), one or more shifters (e.g., barrel shifter(s)) and/or other circuitry may be present. The microprocessor **700** is a semiconductor device fabricated to include many transistors interconnected to implement the structures described above in one or more integrated circuits (ICs) contained in one or more packages. The processor circuitry may include and/or cooperate with one or more accelerators. In some examples, accelerators are implemented by logic circuitry to perform certain tasks more quickly and/or efficiently than can be done by a general purpose processor. Examples of accelerators include ASICs and FPGAs such as those discussed herein. A GPU or other programmable device can also be an accelerator. Accelerators may be on-board the processor circuitry, in the same chip package as the processor circuitry and/or in one or more separate packages from the processor circuitry.

(87) FIG. 8 is a block diagram of another example implementation of the processor circuitry **512** of FIG. 5 and/or the processor circuitry **612** of FIG. 6. In this example, the processor circuitry **512** of FIG. 5 and/or the processor circuitry **612** of FIG. 6 is implemented by FPGA circuitry **800**. For example, the FPGA circuitry **800** may be implemented by an FPGA. The FPGA circuitry **800** can be used, for example, to perform operations that could otherwise be performed by the example microprocessor **700** of FIG. 7 executing corresponding machine readable instructions. However, once configured, the FPGA circuitry **800** instantiates the machine readable instructions in hardware

and, thus, can often execute the operations faster than they could be performed by a general purpose microprocessor executing the corresponding software.

(88) More specifically, in contrast to the microprocessor **700** of FIG. 7 described above (which is a general purpose device that may be programmed to execute some or all of the machine readable instructions represented by the flowcharts of FIGS. 3 and/or 4 but whose interconnections and logic circuitry are fixed once fabricated), the FPGA circuitry **800** of the example of FIG. 8 includes interconnections and logic circuitry that may be configured and/or interconnected in different ways after fabrication to instantiate, for example, some or all of the machine readable instructions represented by the flowcharts of FIGS. 3 and/or 4. In particular, the FPGA circuitry **800** may be thought of as an array of logic gates, interconnections, and switches. The switches can be programmed to change how the logic gates are interconnected by the interconnections, effectively forming one or more dedicated logic circuits (unless and until the FPGA circuitry **800** is reprogrammed). The configured logic circuits enable the logic gates to cooperate in different ways to perform different operations on data received by input circuitry. Those operations may correspond to some or all of the software represented by the flowcharts of FIGS. 3 and/or 4. As such, the FPGA circuitry **800** may be structured to effectively instantiate some or all of the machine readable instructions of the flowcharts of FIGS. 3 and/or 4 as dedicated logic circuits to perform the operations corresponding to those software instructions in a dedicated manner analogous to an ASIC. Therefore, the FPGA circuitry **800** may perform the operations corresponding to the some or all of the machine readable instructions of FIGS. 3 and/or 4 faster than the general purpose microprocessor can execute the same.

(89) In the example of FIG. 8, the FPGA circuitry **800** is structured to be programmed (and/or reprogrammed one or more times) by an end user by a hardware description language (HDL) such as Verilog. The FPGA circuitry **800** of FIG. 8, includes example input/output (I/O) circuitry **802** to obtain and/or output data to/from example configuration circuitry **804** and/or external hardware **806**. For example, the configuration circuitry **804** may be implemented by interface circuitry that may obtain machine readable instructions to configure the FPGA circuitry **800**, or portion(s) thereof. In some such examples, the configuration circuitry **804** may obtain the machine readable instructions from a user, a machine (e.g., hardware circuitry (e.g., programmed or dedicated circuitry) that may implement an Artificial Intelligence/Machine Learning (AI/ML) model to generate the instructions), etc. In some examples, the external hardware **806** may be implemented by external hardware circuitry. For example, the external hardware **806** may be implemented by the microprocessor **700** of FIG. 7. The FPGA circuitry **800** also includes an array of example logic gate circuitry **808**, a plurality of example configurable interconnections **810**, and example storage circuitry **812**. The logic gate circuitry **808** and the configurable interconnections **810** are configurable to instantiate one or more operations that may correspond to at least some of the machine readable instructions of FIGS. 3 and/or 4 and/or other desired operations. The logic gate circuitry **808** shown in FIG. 8 is fabricated in groups or blocks. Each block includes semiconductor-based electrical structures that may be configured into logic circuits. In some examples, the electrical structures include logic gates (e.g., And gates, Or gates, Nor gates, etc.) that provide basic building blocks for logic circuits. Electrically controllable switches (e.g., transistors) are present within each of the logic gate circuitry **808** to enable configuration of the electrical structures and/or the logic gates to form circuits to perform desired operations. The logic gate circuitry **808** may include other electrical structures such as look-up tables (LUTs), registers (e.g., flip-flops or latches), multiplexers, etc.

(90) The configurable interconnections **810** of the illustrated example are conductive pathways, traces, vias, or the like that may include electrically controllable switches (e.g., transistors) whose state can be changed by programming (e.g., using an HDL instruction language) to activate or deactivate one or more connections between one or more of the logic gate circuitry **808** to program desired logic circuits.

(91) The storage circuitry **812** of the illustrated example is structured to store result(s) of the one or more of the operations performed by corresponding logic gates. The storage circuitry **812** may be implemented by registers or the like. In the illustrated example, the storage circuitry **812** is distributed amongst the logic gate circuitry **808** to facilitate access and increase execution speed.

(92) The example FPGA circuitry **800** of FIG. **8** also includes example Dedicated Operations Circuitry **814**. In this example, the Dedicated Operations Circuitry **814** includes special purpose circuitry **816** that may be invoked to implement commonly used functions to avoid the need to program those functions in the field. Examples of such special purpose circuitry **816** include memory (e.g., DRAM) controller circuitry, PCIe controller circuitry, clock circuitry, transceiver circuitry, memory, and multiplier-accumulator circuitry. Other types of special purpose circuitry may be present. In some examples, the FPGA circuitry **800** may also include example general purpose programmable circuitry **818** such as an example CPU **820** and/or an example DSP **822**. Other general purpose programmable circuitry **818** may additionally or alternatively be present such as a GPU, an XPU, etc., that can be programmed to perform other operations.

(93) Although FIGS. **5** and **6** illustrate two example implementations of the processor circuitry **512** of FIG. **5** and/or the processor circuitry **612** of FIG. **6**, many other approaches are contemplated. For example, as mentioned above, modern FPGA circuitry may include an on-board CPU, such as one or more of the example CPU **820** of FIG. **8**. Therefore, the processor circuitry **512** of FIG. **5** and/or the processor circuitry **612** of FIG. **6** may additionally be implemented by combining the example microprocessor **700** of FIG. **7** and the example FPGA circuitry **800** of FIG. **8**. In some such hybrid examples, a first portion of the machine readable instructions represented by the flowcharts of FIGS. **3** and/or **4** may be executed by one or more of the cores **702** of FIG. **7**, a second portion of the machine readable instructions represented by the flowcharts of FIGS. **3** and/or **4** may be executed by the FPGA circuitry **800** of FIG. **8**, and/or a third portion of the machine readable instructions represented by the flowcharts of FIGS. **3** and/or **4** may be executed by an ASIC. It should be understood that some or all of the rover circuitry **112** and/or the base circuitry **122** of FIG. **2** may, thus, be instantiated at the same or different times. Some or all of the circuitry may be instantiated, for example, in one or more threads executing concurrently and/or in series. Moreover, in some examples, some or all of the rover circuitry **112** and/or the base circuitry **122** of FIG. **2** may be implemented within one or more virtual machines and/or containers executing on the microprocessor.

(94) In some examples, the processor circuitry **512** of FIG. **5** and/or the processor circuitry **612** of FIG. **6** may be in one or more packages. For example, the microprocessor **700** of FIG. **7** and/or the FPGA circuitry **800** of FIG. **8** may be in one or more packages. In some examples, an XPU may be implemented by the processor circuitry **512** of FIG. **5** and/or the processor circuitry **612** of FIG. **6**, which may be in one or more packages. For example, the XPU may include a CPU in one package, a DSP in another package, a GPU in yet another package, and an FPGA in still yet another package.

(95) From the foregoing, it will be appreciated that example methods, apparatus and articles of manufacture have been disclosed manage correction requests in a positioning system. The disclosed methods, apparatus and articles of manufacture improve the efficiency of using a computing device by controlling the amount of corrections sent to a GPS rover by using a set of criteria such as an acceptable error metric to only request RTK corrections from a base when they are needed. The disclosed methods, apparatus and articles of manufacture monitor the inaccuracy of the solution and requests corrections only when it needs them, thus significantly reducing the amount of data that is required to navigate but insuring a minimum level of accuracy. The disclosed methods, apparatus and articles of manufacture are accordingly directed to one or more improvement(s) in the functioning of a computer.

(96) Example methods, apparatus, systems, and articles of manufacture to manage correction requests in a positioning system are disclosed herein. Further examples and combinations thereof include the following:

(97) Example 1 includes an apparatus comprising accuracy determination circuitry to determine accuracy of a current position based on location data, correction request circuitry to request location correction data from a reference location when the accuracy does not satisfy a threshold, and correction determination circuitry to adjust the location data with the location correction.

(98) Example 2 includes the apparatus of example 1, wherein the accuracy determination circuitry is to determine the accuracy of the current position based on the adjusted location data.

(99) Example 3 includes the apparatus of example 1, wherein the correction request circuitry is to connect to a correction stream to request the location correction data, the location correction data including corrections for calculations of the current position based on information from satellites.

(100) Example 4 includes the apparatus of example 3, wherein the correction request circuitry is to stop flow of location correction data from the correction stream after the accuracy satisfies the threshold.

(101) Example 5 includes the apparatus of example 1, wherein the correction request circuitry is to request the location correction data from the reference location using a cellular network or an infield network.

(102) Example 6 includes the apparatus of example 1, wherein the correction determination circuitry is to receive the location correction data from the reference location using at least one short message service (SMS) message.

(103) Example 7 includes a method for correcting location data, the method comprising determining accuracy of a current position based on location data, requesting location correction data from a reference location when the accuracy does not satisfy a threshold, and adjusting the location data with the location correction data.

(104) Example 8 includes the method of example 7, further including determining the accuracy of the current position based on the adjusted location data.

(105) Example 9 includes the method of example 7, further including connecting to a correction stream to request the location correction data, the location correction data including corrections for calculations of the current position based on information from satellites.

(106) Example 10 includes the method of example 9, further including stopping flow of location correction data from the correction stream after the accuracy satisfies the threshold.

(107) Example 11 includes the method of example 7, further including requesting the location correction data from the reference location using a cellular network or an infield network.

(108) Example 12 includes the method of claim 7, further including receiving the location correction data from the reference location using at least one short message service (SMS) message.

(109) Example 13 includes a non-transitory computer readable medium comprising instructions that, when executed, cause processor circuitry to at least determine accuracy of a current position based on location data, request location correction data from a reference location when the accuracy does not satisfy a threshold, and adjust the location data with the location correction data.

(110) Example 14 includes the non-transitory computer readable medium of example 13, wherein the instructions, when executed, cause the processor circuitry to determine the accuracy of the current position based on the adjusted location data.

(111) Example 15 includes the non-transitory computer readable medium of example 13, wherein the instructions, when executed, cause the processor circuitry to connect to a correction stream to request the location correction data, the location correction data including corrections for calculations of the current position based on information from satellites.

(112) Example 16 includes the non-transitory computer readable medium of example 15, wherein the instructions, when executed, cause the processor circuitry to stop flow of location correction data from the correction stream after the accuracy satisfies the threshold.

(113) Example 17 includes the non-transitory computer readable medium of example 13, wherein the instructions, when executed, cause the processor circuitry to request the location correction data

from the reference location using a cellular network or an infield network.

(114) Example 18 includes the non-transitory computer readable medium of claim 13, wherein the instructions, when executed, cause the processor circuitry to receive the location correction data from the reference location using at least one short message service (SMS) message.

(115) Although certain example methods, apparatus and articles of manufacture have been disclosed herein, the scope of coverage of this patent is not limited thereto. On the contrary, this patent covers all methods, apparatus and articles of manufacture fairly falling within the scope of the claims of this patent.

(116) The following claims are hereby incorporated into this Detailed Description by this reference, with each claim standing on its own as a separate embodiment of the present disclosure.

Claims

1. An apparatus comprising: interface circuitry; machine-readable instructions; and at least one processor circuit to be programmed by the machine-readable instructions to: determine a first accuracy of a current position based on location data; when the first accuracy does not satisfy a threshold, connect to a correction stream from a reference location; request location correction data from the reference location via the correction stream; adjust the location data based on the location correction data; determine a second accuracy of the adjusted location data; and when the second accuracy satisfies the threshold, disconnect from the correction stream.
2. The apparatus of claim 1, wherein the current position is a first current position, the at least one processor circuit to determine a second current position based on the adjusted location data.
3. The apparatus of claim 1, wherein the location correction data includes corrections for calculations of the current position based on information from satellites.
4. The apparatus of claim 1, wherein the at least one processor circuit is to request the location correction data from the reference location using a cellular network or an infield network.
5. The apparatus of claim 1, wherein the at least one processor circuit is to receive the location correction data from the reference location using at least one short message service (SMS) message.
6. The apparatus of claim 1, wherein the at least one processor circuit is to transmit a request to the reference location, the request to include an identifier associated with a satellite from which the location data was obtained, the location correction data associated with the satellite.
7. The apparatus of claim 1, wherein the at least one processor circuit is to request the location correction data based on subscription to a correction service.
8. A method for correcting location data, the method comprising: determining a first accuracy of a current position based on location data; connecting to a correction stream from a reference location based on the first accuracy not satisfying a threshold; requesting location correction data from the reference location via the correction stream; adjusting the location data based on the location correction data; determining a second accuracy of the adjusted location data; and disconnecting from the correction stream based on the second accuracy satisfying the threshold.
9. The method of claim 8, wherein the current position is a first current position, further including determining a second current position based on the adjusted location data.
10. The method of claim 8, wherein the location correction data includes corrections for calculations of the current position based on information from satellites.
11. The method of claim 8, further including requesting the location correction data from the reference location using a cellular network or an infield network.
12. The method of claim 8, further including receiving the location correction data from the reference location using at least one short message service (SMS) message.
13. A non-transitory computer readable medium comprising instructions that, when executed, cause processor circuitry to at least: determine a first accuracy of a current position based on location

data; when the first accuracy does not satisfy a threshold, connect to a correction stream from a reference location; request location correction data from the reference location via the correction stream; adjust the location data based on the location correction data; determine a second accuracy of the adjusted location data; and when the second accuracy satisfies the threshold, disconnect from the correction stream.

14. The non-transitory computer readable medium of claim 13, wherein the current position is a first current position, and the instructions, when executed, cause the processor circuitry to determine a second current position based on the adjusted location data.

15. The non-transitory computer readable medium of claim 13, wherein the location correction data includes corrections for calculations of the current position based on information from satellites.

16. The non-transitory computer readable medium of claim 13, wherein the instructions, when executed, cause the processor circuitry to request the location correction data from the reference location using a cellular network or an infield network.

17. The non-transitory computer readable medium of claim 13, wherein the instructions, when executed, cause the processor circuitry to receive the location correction data from the reference location using at least one short message service (SMS) message.
