

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                      |
|----------------------|----------------------|
| United States Patent | 12388290             |
| Kind Code            | B2                   |
| Date of Patent       | August 12, 2025      |
| Inventor(s)          | Morozov; Igor et al. |

---

### Backup system, backup interface module, and base plate

---

#### Abstract

Systems, apparatuses, and methods are described for a backup system. The configuration of the backup system in terms of number of load groups, power sources, and/or total power limit may be altered. An interface enclosure of the backup system may include a housing for electric circuitry, where the housing may be a clam-shell design including a base plate and a backup interface module. The base plate may comprise a frame, one or more detachable hinges, and/or two or more multi-terminals. The base plate may include a plurality of multi-terminals. The multi-terminals may be arranged to connect to one or more load groups, power sources, power devices, other multi-terminals, etc. Each load group that is connected to the multi-terminals may be disconnected from the utility grid and connected to the one or more sources of backup power in the case of a utility grid shutdown.

---

**Inventors:** Morozov; Igor (Kfar-Yona, IL), Bakker; Frank (Tel Aviv, IL), Gomberg; Bryon (Kfar Saba, IL)

**Applicant:** Solaredge Technologies Ltd. (Herzeliya, IL)

**Family ID:** 78789750

**Assignee:** Solaredge Technologies Ltd. (Herzeliya, IL)

**Appl. No.:** 18/653179

**Filed:** May 02, 2024

#### Prior Publication Data

| Document Identifier | Publication Date |
|---------------------|------------------|
| US 20240283287 A1   | Aug. 22, 2024    |

#### Related U.S. Application Data

continuation parent-doc US 17534561 20211124 US 12009692 child-doc US 18653179  
us-provisional-application US 63117804 20201124

## Publication Classification

**Int. Cl.:** H02J9/06 (20060101); G06F1/30 (20060101)

**U.S. Cl.:**

**CPC** H02J9/061 (20130101); H02J9/068 (20200101); G06F1/30 (20130101)

## Field of Classification Search

**CPC:** H02J (9/061); H02J (9/068); H02J (3/14); H02J (7/0042); H02J (9/062); H02J (9/06); G06F (1/30); Y04S (20/248); H05K (5/0247)

**USPC:** 307/64

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name    | U.S. Cl.  | CPC         |
|--------------|-------------|------------------|-----------|-------------|
| 5302136      | 12/1993     | St. Germain      | 439/924.1 | H01R 13/631 |
| 5478259      | 12/1994     | Noschese         | N/A       | N/A         |
| 7035115      | 12/2005     | Walesa           | N/A       | N/A         |
| 9137919      | 12/2014     | Dorfer et al.    | N/A       | N/A         |
| 2019/0081458 | 12/2018     | Lapushner et al. | N/A       | N/A         |
| 2020/0336003 | 12/2019     | Narla et al.     | N/A       | N/A         |

### FOREIGN PATENT DOCUMENTS

| Patent No. | Application Date | Country | CPC |
|------------|------------------|---------|-----|
| 9105122    | 12/1990          | DE      | N/A |

### OTHER PUBLICATIONS

Mar. 25, 2022—EP Search Report—EP App. No. 21210276.8. cited by applicant

---

*Primary Examiner:* Tan; Richard

*Attorney, Agent or Firm:* Banner & Witcoff, Ltd.

---

## Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 17/534,561, filed on Nov. 24, 2021, which claims priority to U.S. Provisional Patent Application No. 63/117,969, titled “Backup System” and filed on Nov. 24, 2020, and U.S. Provisional Patent Application No. 63/117,804, titled “Backup Interface Module And Base Plate” and filed on Nov. 24, 2020. Each of the above-identified applications is incorporated by reference herein in its entirety.

## BACKGROUND

(1) Power distribution from an electrical grid to one or more loads within a residence may pass through a main circuit breaker and ground fault protection breakers, where the main circuit breaker may limit the amount of total current (or corresponding power) that all loads in the residence consume at once. When power is not provided by the electrical grid, such as in the case of a power outage or power disconnection, the loads may fail to operate, including critical loads such as a heating load during the winter months. In such a no-backup configuration, the loads will cease to operate and all electrical power at the residence may be shut down. A backup power source may provide power to the residence, thereby allowing un-interrupted operation of the loads. When the backup power is insufficient to provide power for all loads at the residence operating simultaneously, only a part of the loads at the residence may be connected to the backup power source in a partial backup configuration. When the backup power is sufficient to provide power for all loads at the residence operating simultaneously, all of the loads at the residence may be connected to the backup power source in a full backup configuration.

(2) When an electrical utility outage occurs, it is useful for critical loads such as pumps, security systems, refrigerators, and electronics to have a backup source of power available (e.g., a generator or a backup electrical power source). A generator is a device that converts motive power (e.g., mechanical energy) into electrical power for use in an external circuit. Sources of mechanical energy may include steam turbines, gas turbines, water turbines, internal combustion engines, wind turbines, and even hand cranks. Examples of backup electrical power sources include solar panels, wind turbines, batteries, and super-capacitors.

## SUMMARY

(3) The following summary presents a simplified summary of certain features. The summary is not an extensive overview and is not intended to identify key or critical elements.

(4) One or more electrical loads may be collected into groups (hereinafter referred to as “load groups”) where each load group may have different priorities for backup power when grid power is unavailable. For example, a first load group may be a group of critical loads that require backup power, and a second load group may be non-critical and not require backup power. An interface enclosure for partially or fully supplying power to the one or more load groups may be described herein. The interface enclosure may be a backup interface enclosure including electric circuitry (e.g., one or more relays, one or more detection circuits, one or more power devices, etc.) for disconnecting one or more loads from a connection to the utility grid in the case of a shutdown of the utility grid (e.g., when the utility grid is not providing power). The interface enclosure may disconnect (e.g., in the case of shutdown) one or more load groups so that the one or more load groups may be safely connected to one or more sources of backup power (e.g., one or more photovoltaic (PV) sources, or one or more electrical storage devices such as batteries). This may have the advantage of allowing the one or more sources of backup power and the one or more loads to form a local grid (e.g., a “microgrid”) separate from the utility grid. When the utility grid returns to normal, and is available for supplying power again to the loads, the interface enclosure may connect the loads to the utility grid.

(5) The interface enclosure may include a housing for electric circuitry, where the housing may be a clam-shell design including a base plate and a backup interface module. The base plate may comprise a frame, one or more detachable hinges, and/or two or more multi-terminals. Each multi-terminal may include one or more terminal connections, where each terminal connection may be configured for connecting the backup interface module to the base plate (mechanically or electrically), connecting load groups, and/or connecting power sources. The base plate may serve as a mount for the backup interface module, and the backup interface module may include electronics for managing the backup interface connections (e.g., circuitry, relays, communication interfaces/devices, cooling devices, etc.). The base plate may be configured to support the backup

interface module, serve as a part of the interface enclosure protecting the circuitry, and/or connect the backup interface module to a mounting. The base plate may be sized or arranged for the interface enclosure to be located inside of or connected to the mounting. The mounting may contain a plurality of load groups. The mounting may be an electrical distribution panel.

(6) The backup interface module may include lugs protruding from the backup interface module, which may be configured to mechanically connect or electrically connect the backup interface module to the multi-terminals of the base plate. The backup interface module may include electronics (e.g., the backup interface module may comprise the circuitry and components found in a power device case). The backup interface module may be mechanically connected to the base plate using one or more detachable hinge connections. A detachable hinge connection may include a portion of the backup interface module (e.g., a protuberance or an axis) and a curved track. The one or more curved tracks may be part of or connected to the base plate, and may be arranged to receive the axis. The detachable hinge connection may be a hinged connection that allows the backup interface module to rotate relative to the base plate along the axis. For example, the curved track may be part of, or connected to, the frame of the base plate and an axis protuberance may be connected to the backup interface module. For example, the axis protuberance may be part of or connected to the frame of the base plate and the curved track may be connected to the backup interface module.

(7) The base plate may include a plurality of multi-terminals. The multi-terminals may be arranged to connect to one or more load groups, power sources, power devices, and/or other multi-terminals, etc. Each load group that is connected to the multi-terminals may be disconnected from the utility grid and connected to the one or more sources of backup power in the case of a utility grid shutdown. Connecting only some of the load groups to the multi-terminals may provide a partial backup to only those connected load groups (e.g., one or more load groups that are connected to critical loads). Connecting all of the load groups to the multi-terminals may provide a full backup to the connected load groups (e.g., one or more load groups that are connected to critical loads and one or more load groups that are connected to non-critical loads). Connecting none of the load groups to the multi-terminals may provide no backup to the one or more multi-terminals. This arrangement may allow field-configurable connection configurations for operations of the backup interface enclosure and the electrical supply system as no backup, partial backup, or full backup.

(8) In some examples, connecting the backup interface module to the base plate may complete one or more connections between the interface enclosure and one or more other electrical or electronic elements of an electrical network, such as elements of a power generation system panel.

(9) A backup interface module may be configured to be connected to a base, wherein the base may have a base plate with configurable connectors. The base plate may be configured by connecting the configurable connectors to one another. The base plate may be configured by connecting a backup interface module to the base plate. By changing a wiring configuration and/or connecting a backup interface module including relays and/or other switching circuitry to the base plate, various backup configurations may be supported. For example, part, none or all of electrical loads connected to the configurable connectors may be connected to a backup power source in case of an outage of a primary power source. Selection of a particular backup configuration may be manual (e.g., pre-wiring) or automatic (e.g., by a controller configured to select a backup configuration), and may depend on current load and/or backup power production levels.

(10) These and other features and advantages are described in greater detail below.

---

## **Description**

### **BRIEF DESCRIPTION OF THE DRAWINGS**

(1) Some features are shown by way of example, and not by limitation, in the accompanying

drawings. In the drawings, like numerals reference similar elements.

(2) FIG. 1 shows an example electrical supply system with an interface enclosure.

(3) FIG. 2 shows an example interface enclosure.

(4) FIG. 3A shows an example front view of a backup interface module of the interface enclosure.

(5) FIG. 3B shows an example back view of the backup interface module of the interface enclosure.

(6) FIG. 3C shows an example side view of the backup interface module of the interface enclosure.

(7) FIG. 3D shows an example front perspective view of the backup interface module of the interface enclosure.

(8) FIG. 3E shows an example front view of a different backup interface module of the interface enclosure.

(9) FIG. 4A shows an example front view of a base plate of the interface enclosure.

(10) FIG. 4B shows an example back view of the base plate of the interface enclosure.

(11) FIG. 4C shows an example side view of the base plate of the interface enclosure.

(12) FIG. 4D shows an example front perspective view of the base plate of the interface enclosure.

(13) FIG. 5A shows an example side view of a curved track of the interface enclosure.

(14) FIG. 5B shows an example side view of a hinged connection of the interface enclosure.

(15) FIG. 5C shows an example side view of a different curved track of the interface enclosure.

(16) FIG. 6A shows an example two connector multi-terminal of the base plate.

(17) FIG. 6B shows an example three connector multi-terminal of the base plate.

(18) FIG. 6C shows an example four connector multi-terminal of the base plate.

(19) FIG. 7A shows an example side view of a two connector multi-terminal of the base plate.

(20) FIG. 7B shows an example side view of a three connector multi-terminal of the base plate.

(21) FIG. 8A shows an example side view of a different two connector multi-terminal of the base plate.

(22) FIG. 8B shows an example side view of a different three connector multi-terminal of the base plate.

(23) FIG. 9A shows an example front perspective view of a two connector multi-terminal of the base plate.

(24) FIG. 9B shows an example front perspective view of a three connector multi-terminal of the base plate.

(25) FIG. 10 shows an example bottom perspective view of a three connector multi-terminal of the base plate.

(26) FIG. 11 shows an example bottom view of a three connector multi-terminal of the base plate.

(27) FIG. 12A shows an example front view of an interface enclosure.

(28) FIG. 12B shows an example of a portion of an interface enclosure.

(29) FIG. 13 shows an example perspective top view of an interface enclosure.

(30) FIG. 14 shows an example side view of an interface enclosure.

(31) FIG. 15 shows an example view of an interface enclosure with the front cover of the backup interface module removed.

(32) FIG. 16 shows an example front view of a different interface enclosure with the front cover of the backup interface module removed.

(33) FIG. 17A shows an example wiring configuration of a backup system;

(34) FIG. 17B shows an example wiring configuration of a backup system including a backup interface module;

(35) FIG. 18A shows an example wiring configuration of a backup system including a backup interface module;

(36) FIG. 18B shows an example wiring configuration of a backup system including a backup interface module;

(37) FIG. 19A shows an example wiring configuration of a backup system including a backup interface module;

(38) FIG. 19B shows an example wiring configuration of a backup system including a backup interface module;

(39) FIG. 20 shows an example connection between a base plate and a backup interface module;

(40) FIG. 21 shows an example wiring configuration of a backup system including a backup interface module

#### DETAILED DESCRIPTION

(41) An interface enclosure is described herein. The interface enclosure may be a backup interface enclosure including electric circuitry (e.g., one or more relays, one or more detection circuits, one or more power devices, etc.) for disconnecting one or more load groups from a connection to the utility grid when the utility grid is not providing power (e.g., in the case of a shutdown of the utility grid or a blackout). In such a scenario, the interface enclosure may disconnect one or more load groups so that the one or more load groups may be connected to one or more sources of backup power (e.g., one or more photovoltaic (PV) sources, or one or more electrical storage devices such as batteries). This may allow the one or more sources of backup power and the one or more loads to form a local grid (e.g., a “microgrid”) isolated or separate from the utility grid (e.g., until the utility grid is available again). The interface enclosure may be located inside a mounting.

(42) The term “mounting” may refer to an electrical distribution panel/board. Electrical power generation systems, including photovoltaic (PV) systems, may be electrically connected to building loads and feed excess electrical power to the electrical grid, through a circuit breaker/distribution board, a combination service entrance device (CSED), a main breaker box, a load center, an all-in-one electrical distribution board, and/or the like. As used herein, the terms circuit breaker/distribution panel/board, combination service entrance device (CSED), main breaker box, distribution board, meter box, circuit box, electrical box, load center, and/or the like, may be used interchangeably, and mean one or more building electrical supply boxes comprising electrical supply components, including utility/supply/load conductors (e.g., wires or busbars), one or more utility side protection units, one or more power/energy meters, one or more main circuit protection breakers, load side circuit breakers, and/or the like. The building electrical supply components may be located in one or more enclosures or boxes, where some of the boxes may be adjacent. For example, a single all-in-one electrical panel box may be partitioned into a meter enclosure, a main circuit breaker enclosure, a load circuit breakers enclosure, and/or the like. The mounting may contain a plurality of load groups.

(43) The interface enclosure may include a base plate that serves as a mount for the interface enclosure. The base plate may be arranged to support the backup interface module and serve as a base. The base plate may also be sized and arranged for the interface enclosure to be located inside of a mounting. For example, the base plate of the interface enclosure may include a frame for mounting the base plate in an electrical distribution panel.

(44) In some examples, the interface enclosure may also include a backup interface module for jumpers, relays, electrical circuitry, etc. The backup interface module may be configured with a detachable hinge integrated into the base plate and backup interface module, where each hinge includes an axis and one or more curved tracks. The curved tracks may be part of or connected to the base plate or the backup interface module. The curved tracks may be arranged to receive a portion of the backup interface module or base plate. The curved track may have an open end (e.g., that acts as a funnel to accept the axis), a first curved portion of the track with a large radius of curvature, and/or a second part portion of the track with a smaller radius (e.g., a hook or the letter “J”). The detachable hinge may be a pivoting connection that allows the backup interface module to be rotated relative to the base plate along a connection axis. For example, the curved track may be part of, or connected to, the frame of the base plate.

(45) The base plate may include a plurality of multi-terminals. The multi-terminals may be arranged to connect to one or more load groups, power sources, power devices, other multi-terminals, etc. Each load group that is connected to the multi-terminals may be disconnected from

the utility grid and connected to the one or more sources of backup power in the case of a utility grid shutdown. Connecting only some of the load groups to the multi-terminals may provide a partial backup to only those connected load groups (e.g., one or more load groups that are connected to critical loads). Connecting all of the load groups to the multi-terminals may provide a partial or full backup to the connected load groups (e.g., one or more load groups that are connected to critical loads or one or more load groups that are connected to non-critical loads). Connecting none of the load groups to the multi-terminals may provide no backup to the one or more multi-terminals. In applications without backup support for load groups, load groups may be connected to the multi-terminals and jumpers may be installed to short between the load groups and one or more power sources. The jumpers may be electrical cables connecting one multi-terminal to another. The jumpers may be installed in the backup interface module and connect the multi-terminals, such as when the backup interface module is mechanically and electrically connected to the base plate. The multi-terminals, jumpers, and/or cover may allow configuring the operation of the backup interface enclosure or the electrical supply system to support different backup configurations. For example, electrically connecting the multi-terminals of the grid and load groups may provide a no-backup configuration. Electrically connecting some of the load groups to the grid through a relay, and other load groups to the grid using a relay, may provide a partial-backup configuration. Electrically connecting all of the load groups to the grid through a relay may provide a full-backup configuration. Electrically connecting all of the load groups to the grid (e.g., each through a separate relay) may provide a dynamic full-backup configuration (e.g., wherein load groups may be connected or disconnected based on available power sources, expected consumption, or expected time to grid power availability).

(46) In some examples, connecting the backup interface module to the base plate may complete one or more connections between the interface enclosure and one or more other elements of the electrical supply system.

(47) The accompanying drawings, which form a part hereof, show examples of the disclosure. It is to be understood that the examples shown in the drawings and/or discussed herein are non-exclusive and that there are other examples of how the disclosure may be practiced.

(48) It is noted that the teachings of the presently disclosed subject matter are not bound by the systems and apparatuses described with reference to the figures. Equivalent and/or modified functionality may be consolidated or divided in another manner and may be implemented in any appropriate combination. For example, power source **102** and system power device **108**, which are shown as separate units (shown, for example, in FIG. **1**), may have their functionalities and/or components combined into a single unit.

(49) It is also noted that like references in the various figures may refer to like elements throughout this disclosure. Similar reference numbers may also connote similarities between elements. For example, it is to be understood that backup interface enclosure **200** shown in FIG. **1** may be similar to, or the same as, other interface enclosures described and shown herein, and vice versa. Throughout this disclosure certain general references may be used to refer to any of the specific related elements. For example, backup interface enclosure **200** may refer to any of the various interface enclosures.

(50) It is also noted that all numerical values given in the examples of the description are provided for purposes of example only and are by no means binding.

(51) The terms “substantially” and “about” are used herein to indicate variations that are equivalent for an intended purpose or function (e.g., within a permissible variation range). Certain values or ranges of values are presented herein with numerical values being preceded by the terms “substantially” and “about”. The terms “substantially” and “about” are used herein to provide literal support for the exact number that it precedes, as well as a number that is near to or approximately the number that the term precedes. In determining whether a number is near to or approximately a specifically recited number, the near or approximating un-recited number may be a

number, which, in the context in which it is presented, provides a substantial equivalent of the specifically recited number.

(52) FIG. 1 shows an example of an electrical supply system **100** with an interface enclosure **200**.

(53) Electrical supply system **100** may include one or more power sources **102**. As an example, the one or more power sources **102** may be one or more photovoltaic (PV) generators. For example, power sources **102** may be one or more photovoltaic cells, strings of substrings of photovoltaic cells, and/or strings of photovoltaic panels/modules. Although power sources are described herein in the context of PV generators, the term power source may include other types of appropriate power sources, such as wind turbines, hydro-turbines, fuel cells, etc.

(54) The one or more power sources **102** may be connected via one or more system power devices **108** to one or more mountings **110**. The one or more system power devices **108** may be, for example, one or more: DC to DC converters (e.g., buck converters, boost converters, buck/boost converters, buck+boost converters, etc.), DC to AC inverters, combiner and/or monitoring boxes, etc. The one or more system power devices **108** may comprise an inverter for one or more phases (e.g., one phase inverter, two phase inverter, three-phase inverter, etc.), and may comprise lines or phases that are not shown herein for the sake of simplicity.

(55) The one or more power sources may also be connected to one or more electricity storage devices **104** (e.g., batteries). The one or more electricity storage devices **104** may be connected to one or more mountings **110** directly or via one or more system power devices **108**. The one or more electricity storage devices **104** may be connected to the utility grid **106**.

(56) While two load groups are shown in the example of FIG. 1, any appropriate number of load groups may be possible. Each of load groups **112A** and **112B** may be one or more electrical loads **114**, such as an appliance, a heater, a pump, an air conditioning unit, etc. Each of the load groups **112A** and **112B** may be a sub load group, sub panel, split panel, etc. Each mounting **110** may be connected to the utility grid **106**. The mounting **110** may contain a plurality of load groups **112A** and **112B**. The mounting **110** may be an electrical distribution panel. Each load group **112A** and **112B** may receive a priority label. Each of the priority labels may be different or the same as another priority label. As an example, load group **112A** may be connected to critical loads and given a “high priority” priority label or an “always backup” priority label. Load group **112B** may be connected to non-critical loads and given a “lower priority” priority label or a “may not need backup” priority label.

(57) A backup interface enclosure **200** may be mounted or otherwise housed inside or in proximity to the mounting **110**. Backup interface enclosure **200** may be connected to one or more of the load groups **112A** and **112B**. Backup interface enclosure **200** may be arranged to provide backup power to the one or more load groups **112A** and/or **112B** that are connected to the backup interface enclosure. The backup interface enclosure **200** may include one or more relays, detection circuits, and/or power devices. The one or more relays may be arranged to disconnect the one or more load groups **112A** and/or **112B** from the utility grid **106** (e.g., in the case the utility grid **106** is not providing power due to a utility grid shutdown). The one or more detection circuits may be arranged to detect whether the utility grid **106** is, or is not, providing power. The one or more power devices may be arranged to convert power. For example, if the utility grid **106** is shut down and not providing power, the backup interface enclosure **200** may disconnect one or more of the load groups **112A** and/or **112B** from the utility grid, which may provide backup power to the one or more of the load groups **112A** and/or **112B** from one or more backup power sources. The one or more backup power sources may be the one or more power sources **102** and/or the one or more electricity storage devices **104**.

(58) How the load groups **112A** and **112B** are connected to the backup interface enclosure **200** may at least partially determine whether the backup interface enclosure **200** provides full backup, partial backup, or no backup. For example, if both load groups **112A** and **112B** are connected to the backup interface enclosure **200**, then the backup interface enclosure **200** may provide full backup.



If only one of the load groups **112A** or **112B** is connected to the backup interface enclosure **200**, then the backup interface enclosure **200** may provide partial backup to the connected load group **112A** or **112B**. If both load groups **112A** and **112B** are not connected to the backup interface enclosure **200**, then the backup interface enclosure **200** may provide no backup. For example, the load groups **112A** and **112B** and utility grid **106** may remain connected to a base plate **400A** (as may be shown, for example, in FIG. 2) of the backup interface enclosure **200**, and (e.g., depending on what type of backup is arranged) there may be jumpers and/or relays connected. For example, when there is no backup arranged, there may be only jumpers connected to the base plate **400A** of the backup interface enclosure **200**. When there is partial backup arranged, both jumpers and relays may be connected to the base plate **400A** of the backup interface enclosure **200**. And when full backup is arranged, all of the load groups **112A** and **112B** may have relays connected to the base plate **400A** that are configured to disconnect the load groups **112A** and **112B** from the utility grid **106** (e.g., when there is no grid power).

(59) FIG. 2 shows an example of a backup interface enclosure **200A**. Backup interface enclosure **200A** may include a backup interface module **300A** and a base plate **400A**. Backup interface enclosure **200A** may also be referred to as a “cover”. Base plate **400A** may also be referred to as a “base”. Backup interface module **300A** may contain electronic circuitry (e.g., one or more relays, detection circuits, power devices, transformers, automatic transfer relays, cooling devices, etc.). Backup interface module **300A** may be mounted to base plate **400A**. Base plate **400A** may be mounted inside an electrical mounting **110**. Base plate **400A** may include a plurality of multi-terminals **600**. Each of the multi-terminals **600** may include a plurality of terminal connectors **606** (as may be shown, for example, in FIGS. 6A to 11). The base plate **400A** of FIG. 2 may have a plurality of two connector multi-terminals **602** and a plurality of three connector multi-terminals **603**. One or more of the multi-terminals **600** may be connected to the backup interface module **300A** via electromechanical connectors **302** (as may be shown, for example, in FIG. 3A).

(60) Reference is now made to FIGS. 3A to 3D, which show examples of a backup interface module **300A** according to examples of the present subject matter. Backup interface module **300A** may include one or more electromechanical connectors **302** (e.g., lugs), a front cover **305**, a back cover **306** (as may be shown, for example, in FIG. 3B), one or more heat dispersing elements **304** (as may be shown, for example, in FIG. 3B), and/or one or more protuberances **308A** (as may be shown, for example, in FIG. 3B). Electronic circuitry of the backup interface module **300A** may be housed inside the backup interface module **300A**. For example, electronic circuitry of the backup interface module **300A** may be housed between the front cover **305** and the back cover **306** of the backup interface module **300A**.

(61) The electromechanical connectors **302** may be cable lugs or wire lugs that are arranged to provide mechanical or electrical connections between elements of the electrical supply system **100**. The electromechanical connectors **302** may facilitate a connection between electronics of the backup interface module **300A** and one or more multi-terminals **600** of the base plate **400**. For example, the electromechanical connectors **302** may each be connected to a corresponding terminal connector **606** of a multi-terminal. As an example, an electromechanical connector **302** may be connected to a corresponding terminal connector **606** using a fastening element **608** (as may be shown, for example, in FIG. 16). Fastening element **608** may be a metallic screw or bolt configured to electromechanically connect between the multi-terminals **600** of the base plate and the backup interface module **300A**. One or more of the multi-terminals **600** of the base plate **400A** may be connected to one or more of the load groups **112A** and **112B** and/or to one or more other multi-terminals **600**. Fastening elements **608** and electromechanical connector **302** may be arranged to pass relatively high current (e.g., between a power source and a load via one or more multi-terminals **600** and the backup interface module **300A**). Fastening element **608** and electromechanical connectors **302** may provide a relatively reliable and relatively quick connection between the one or more multi-terminals **600** and the backup interface module **300A**. Backup

interface module **300A** may include one or more corresponding electromechanical connectors housed inside the backup interface module **300A**. The one or more corresponding electromechanical connectors may be connected to the electronic circuitry or one or more jumpers housed inside the backup interface module **300A**. The one or more corresponding electromechanical connectors **302** may be connected to the electronic circuitry or one or more jumpers using one or more fastening elements housed inside the backup interface module **300A**. (62) Electromechanical connectors **302** may also be referred to as “backup interface module terminals” or “cover terminals.” Multi-terminals **600** may also be referred to as “base multi-terminals.”

(63) With reference to FIG. **3B**, the one or more heat dispersing elements **304** may be configured to provide thermal heat dissipation. For example, the one or more heat dispersing elements **304** may be configured to provide dissipation of a thermal heat that is related to the electronics housed inside the backup interface module **300A**. The one or more heat dispersing elements **304** may also be configured to provide mechanical stiffness to the back cover **306** of backup interface module **300A**. For example, the one or more heat dispersing elements **304** may be one or more physical fins extending relatively perpendicularly from the back cover **306** of backup interface module **300A**. The physical fins **304** may mechanically strengthen the back cover **306**, and dissipate heat generated by electronics located in the backup interface module **300A**.

(64) The interface enclosure **200A** may have both a back cover **306** of the backup interface module **300A** as well as a base plate **400A** (e.g., which may serve as a second “back cover” of the interface enclosure **200A**).

(65) Each of the one or more protuberances **308A** may be arranged to be received by a corresponding curved track **500** (as may be shown, for example, in FIG. **5A**) of the base plate **400A**. The one or more protuberances **308A** may be arranged to have an extending member portion (e.g., a protuberance) that is received in and guided by the curved track **500** until it reaches an end of the curved track **500**. The end of the curved track **500** may be arranged to hold the given protuberance **308A** relatively in place, but allow for a rotation of the given protuberance **308A** along a rotational axis of the protuberance **308A**. Curved track **500** together with protuberance **308A** may also be referred to as a “hinge.”

(66) Reference is now made to FIG. **3E**, which shows a backup interface module **300E** according to examples of the present subject matter. Backup interface module **300E** may include one or more protuberances **308E** that extend beyond the side walls of the backup interface module **300E**.

(67) Reference is now made to FIGS. **4A** to **4D**, which show examples of a base plate **400A** according to examples of the present subject matter. Base plate **400A** may include a plurality of multi-terminals **600**, a frame **402**, one or more frame mounting elements **404**, a front **405**, a back **406** (as may be shown, for example, in FIG. **4B**), one or more sides **408** (as may be shown, for example, in FIG. **4C**), and/or one or more curved tracks **500**.

(68) With reference to FIG. **4A**, base plate **400A** may include a rail **900** that has an aperture **902** formed by a pair of rail members **904**. Rail **900** may be arranged to support one or more multi-terminals **600**. The one or more multi-terminals **600** may be secured to base plate **400A** by connecting a support member **708** (as may be shown, for example, in FIGS. **7A-10**) to the rail **900** by placing the support member **708** into the aperture **902**.

(69) The plurality of multi-terminals **600** may include a plurality of two connector multi-terminals **602** with two terminal connectors **606** (as may be shown, for example, in FIG. **6A**) or a plurality of three connector multi-terminals **603** with three terminal connectors **606** (as may be shown, for example, in FIG. **6B**). One or more of the multi-terminals **600** may be quick connect terminals. For example, one or more of the multi-terminals **600** may comprise a socket arranged to receive a plug having preset wiring arrangements. The plug or plugs may be used to determine an operation of the backup interface enclosure **200**. One or more terminal connectors **606** of a multi-terminal **600** may be quick connect terminals, and one or more terminal connectors **606** of that same multi-terminal

**600** may be non-quick connect terminals. For example, a non-quick connect terminal may include a fastening element such as a screw or a bolt that is fastened to the terminal connector **606** of the multi-terminal **600** to secure a connection to the multi-terminal **600**.

(70) The base plate **400A** may include at least three multi-terminals **600**, where each of those at least three multi-terminals **600** has two or more terminal connectors **606**.

(71) The frame **402** may be sized and arranged to fit inside a mounting **110**. For example, the frame **402** may be configured to mechanically connect within the mounting **110**.

(72) The one or more frame mounting elements **404** may be one or more apertures sized and arranged to help connect the base plate **400A** to a surface (e.g., a surface of the mounting **110**). For example, the one or more frame mounting elements **404** may be used to secure the frame **402** to the surface using any appropriate additional connection elements (e.g., one or more screws, bolts, nails, etc.).

(73) The one or more sides **408** may extend relatively perpendicularly from the front **405** of the frame **402**. In some examples, each curved track **500** is located on, or attached to, one of the sides **408** of the frame **402** of the base plate **400A**.

(74) Each of the one or more curved tracks **500** may be sized and arranged to receive and hold a protuberance **308** of the backup interface module **300A**. For example, the curved track **500** of a base plate **400A** may be configured for accepting a protuberance **308** of the backup interface module **300A** to form a hinge. The curved track **500** may be configured for aligning the cover terminals **302** with the base multi-terminals **600**. For example, when the one or more protuberances **308** of the backup interface module **300A** are received by the curved track **500** of the base plate **400A** it may help align one or more electromechanical connectors **302** of the backup interface module **300A** with one or more terminal connectors **606** of one or more multi-terminals **600** of the base plate **400A**.

(75) Reference is now made to FIGS. 5A and 5B, which show examples of a curved track **500A** according to examples of the present subject matter. Curved track **500A** may include a tab **502A**, a funnel region **504A**, a curved central track region **510A**, a curved end track region **512A**, and/or a track path **514A**.

(76) Tab **502A** may extend from a portion of the side **408A** of frame **402A**. Tab **502A** may have one or more convex curved portions that together with one or more complementary, correlated concave curved portions form a gap (e.g., that may be arranged to serve as a slot for a guided member portion of the backup interface module **300A** to be fitted into and slid along). This may provide a hinged connection that may allow the backup interface module **300A** to rotate relative to the base plate **400A** along a rotational axis of the connection.

(77) Funnel region **504A** may include a first edge **506A** and a second edge **508A**. In some examples, funnel region **504A** may be defined by the first edge **506A** and the second edge **508A**. First edge **506A** may be part of tab **502A** and second edge **508A** may be part of the side **408A** of frame **402A**. The funnel region **504A** may be connected to the curved central track region **510A**. A distance between the two edges **506A** and **508A** may increase as a distance from the curved central track **510A** towards the widening mouth of the funnel region **504A** increases. The wide mouth of the funnel region **510A** may help the curved track **500A** to more easily receive the protuberance **308** of the backup interface module **300**. In some examples, one or both of the edges **506A** and **508A** may be curved edges. The two edges **506A** and **508A** may be non-parallel edges.

(78) The curved central region **510A** may be connected to the curved end track region **512A**. The curved central region **510A** may have a first radius **R1**, and the curved end track region may have a second radius **R2**. The radius **R2** of the curved end track region **512A** may be less than the radius **R1** of the curved central track region **510A**. For example, the radius **R2** of the curved end track region **512A** may be substantially less than the radius **R1** of the curved central track region **510A** (e.g., radius **R2** may be at least 10% less than radius **R1**). For example, the radius **R2** of the curved end track region **512A** may be in a range of between about 5 mm to about 45 mm, and the radius

R1 of the curved central track region **510A** may be in a range of between about 20 mm to about 50 mm. As a further example, radius R2 may be about 10 mm and radius R1 may be about 30 mm. Radius R1 may also be sized in accordance with a protuberance **308** of the backup interface module **300** (e.g., according to a radius of the protuberance **308**).

(79) Funnel region **504A** may include a first edge **506A** and a second edge **508A**. First edge **506A** may be part of tab **502A** and second edge **508A** may be part of the side **408A** of frame **402A**. The funnel region **504A** may be connected to the curved central track region **510A**. A distance between the two edges **506A** and **508A** may increase as a distance from the curved central track **510A** towards the widening mouth of the funnel region **504A** increases. The wide mouth of the funnel region **510A** may help the curved track **500A** to more easily receive the protuberance **308** of the backup interface module **300**.

(80) Track path **514A** may be the intended path for the protuberance **308** to be guided along the curved track **510A** to connect the backup interface module **300** to the base plate **400**. Connecting the backup interface module **300** to the base plate **400** may complete one or more connections between the interface enclosure **200** and one or more other elements of the electrical supply system **100**.

(81) FIG. 5B shows an example protuberance **308** inside the curved end track region **512** of the curved track **500**, which may hingedly connect the backup interface module **300** to the base plate **400A**.

(82) Reference is now made to FIG. 5C, which shows a curved track **500B** according to examples of the present subject matter. Curved track **500B** may include a tab **502B**, a funnel region **504B**, a curved central track region **510B**, a curved end track region **512B**, and/or a track path **514B**. Curved track **500B** may include a funnel region **504B** with one or more edges **506B** and **508B** that are straight and/or linear, not curved edges. The two edges **506B** and **508B** may be non-parallel edges. For example, the curved track **500A** of FIGS. 5A and 5B may be similar to the shape of a “C” (C-shaped), and the curved track **500B** of FIG. 5C may be similar to the shape of a “J” (J-shaped).

(83) FIGS. 6A to 6C show examples of multi-terminals **600** according to examples of the present subject matter.

(84) Reference is now made to FIG. 6A, which shows a front view of an example two connector multi-terminal **602** according to examples of the present subject matter. Two connector multi-terminal **602** may include a first terminal connector **606A** and a second terminal connector **606B**. First terminal connector **606A** may be a terminal connector **606** arranged to connect multi-terminal **602** to backup interface module **300A** (e.g., using a fastening element **608** to secure the multi-terminal **600** to an electromechanical connector **302** of the backup interface module **300**). Second terminal connector **606B** may be a terminal connector **606** arranged to connect multi-terminal **602** to one or more other elements of the electrical supply system **100** (e.g., a backup interface module **300**, a different multi-terminal **600**, a power source **102**, one or more load groups **112**, etc.). Terminal connectors **606** may be quick connect terminals or terminals with one or more fastening elements. The terminal connectors **606** of a given multi-terminal **600** may be arranged so that each of the terminal connectors **606** is electrically connected to one another. For example, the multi-terminal **600** may include one or more electricity conducting elements arranged to electrically interconnect the terminal connectors **606** of the multi-terminal **600**. As an example, a metallic portion or busbar may be housed inside multi-terminal **600** in proximity to the terminal connectors **606**. As another example, one or more of the fastening elements **608** of the multi-terminal **600** may be arranged as electricity conducting elements arranged to electrically interconnect the terminal connectors **606** of the multi-terminal **600**. As another example, one or more electrical conductors of one or more elements of the electrical supply system **100** may be arranged as electricity conducting elements arranged to electrically interconnect the terminal connectors **606** of the multi-terminal **600**, such as jumpers. The term “jumper” may also be referred to as a “jump wire,” “jumper wire,”

“jumper cable,” or “cable.” The term “jumper” may refer to one or more electrical wires, one or more electrical cables, one or more electrical busbars, etc., and/or any other appropriate electrical conductor used to make an electrical connection between a plurality of entities in an electrical circuit.

(85) Reference is now made to FIG. 6B, which shows a front view of an example three connector multi-terminal **603** according to examples of the present subject matter. Three connector multi-terminal **603** may include a first terminal connector **606A**, a second terminal connector **606B**, and a third terminal connector **606C**. First terminal connector **606A** may be a terminal connector **606** arranged to connect multi-terminal **602** to backup interface module **300A** (e.g., using a fastening element **608** to secure the multi-terminal **600** to an electromechanical connector **302** of the backup interface module **300A**). Second terminal connector **606B** and third terminal connector **606C** may be terminal connectors **606** arranged to connect multi-terminal **602** to one or more other elements of the electrical supply system **100** (e.g., a backup interface module **300A**, a different multi-terminal **600**, a power source **102**, one or more load groups **112**, etc.). Terminal connectors **606** may be quick connect terminals or terminals with one or more fastening elements.

(86) Reference is now made to FIG. 6C, which shows a front view of an example four connector multi-terminal **604** according to examples of the present subject matter. Four connector multi-terminal **604** may include a first terminal connector **606A**, a second terminal connector **606B**, a third terminal connector **606C**, and a fourth terminal connector **606D**. First terminal connector **606A** may be a terminal connector **606** arranged to connect multi-terminal **602** to backup interface module **300A** (e.g., using a fastening element **608** to secure the multi-terminal **600** to an electromechanical connector **302** of the backup interface module **300A**). Second terminal connector **606B**, third terminal connector **606C**, and fourth terminal connector **606D** may be terminal connectors **606** arranged to connect multi-terminal **602** to one or more other elements of the electrical supply system **100** (e.g., a backup interface module **300A**, a different multi-terminal **600**, a power source **102**, one or more load groups **112**, etc.). Terminal connectors **606** may be quick connect terminals or terminals with one or more fastening elements.

(87) There may be N terminal connectors **606A . . . 606N**, where N is any appropriate number.

(88) Each of the terminal connectors **606A-606N** may be configured to electrically or mechanically connect to a power device (e.g., backup interface module **300A**), a power source **102**, a load group **112A** or **112B**, and/or at least one other terminal connector **606** of a different multi-terminal **600**, etc.

(89) For example, with reference to the three connector multi-terminal **603** of FIG. 6B, the first terminal connector **606A** may be configured to electrically or mechanically connect to a power device, the second terminal connector **606B** may be configured to connect to a power source **102** or a load group **112A** or **112B**, and the third terminal connector **606C** may be configured to connect to at least one other terminal connector **606** of a different multi-terminal **600**.

(90) FIGS. 7A and 7B show examples of multi-terminals **600** according to examples of the present subject matter.

(91) Reference is now made to FIG. 7A, which shows a side view of an example two connector multi-terminal **602A** according to examples of the present subject matter. Two connector multi-terminal **602A** may include a first terminal connector **606A** and a second terminal connector **606B**. Two connector multi-terminal **602A** may also include a support member **708** for connecting the multi-terminal **602A** to the base plate **400A**. For example, base plate **400A** may include a rail **900** that has an aperture **902** formed by a pair of rail members **904** (as may be shown, for example, in FIGS. 4A and 12B). Multi-terminal **602A** may be secured to base plate **400A** by connecting the support member **708** to the rail **900** by placing the support member **708** into the aperture **902** (e.g., between the rail members **904**). In some examples, the rail members **904** may be surfaces of a recess formed in the base plate **400A** to form the aperture **902** of the rail **900**.

(92) Reference is now made to FIG. 7B, which shows a side view of an example three connector

multi-terminal **603A** according to examples of the present subject matter. Three connector multi-terminal **603A** may include a first terminal connector **606A**, a second terminal connector **606B**, and a third terminal connector **606C**. Three connector multi-terminal **603A** may also include a support member **708** for connecting multi-terminal **603A** to the base plate **400A**.

(93) FIGS. **8A** and **8B** show examples of multi-terminals **600** according to examples of the present subject matter.

(94) Reference is now made to FIG. **8A**, which shows a side view of an example two connector multi-terminal **602B** according to examples of the present subject matter. Two connector multi-terminal **602B** may include a first terminal connector **606A** and a second terminal connector **606B**. Two connector multi-terminal **602B** may also include a plurality of support members **708** for connecting multi-terminal **602B** to the base plate **400A**. For example, base plate **400A** may include a plurality of rails **900** that each have an aperture **902** formed by a pair of rail members **904** (as may be shown, for example, in FIG. **12B**). Multi-terminal **602B** may be secured to base plate **400** by connecting the plurality of support members **708** to the plurality of rails **900** by placing each support member **708** into a corresponding aperture **902**. There may be N support members **708**, and N corresponding apertures **902**, where N is any appropriate number. Each pair of support members **708** may form a support aperture **810**. When multi-terminal **602B** is connected to the base plate **400** one or more rail members **904** of the plurality of rails **900** may be placed into support aperture **810**. The plurality of support members **708** and the one or more support apertures **810** may provide additional stability to the connection of the multi-terminal **602B** to the base plate **400**.

(95) Reference is now made to FIG. **8B**, which shows a side view of an example three connector multi-terminal **603B** according to examples of the present subject matter. Three connector multi-terminal **603B** may include a first terminal connector **606A**, a second terminal connector **606B**, and a third terminal connector **606C**. Three connector multi-terminal **603B** may also include a plurality of support members **708** and one or more support apertures **810** for connecting multi-terminal **603B** to the base plate **400A**. There may be N support members **708** and N corresponding apertures **902**, where N is any appropriate number.

(96) FIGS. **9A** and **9B** show examples of multi-terminals **600** according to examples of the present subject matter.

(97) Reference is now made to FIG. **9A**, which shows a top perspective view of an example two connector multi-terminal **602B** according to examples of the present subject matter. Two connector multi-terminal **602B** may include a first terminal connector **606A** and a second terminal connector **606B**. Two connector multi-terminal **602B** may also include a plurality of support members **708** and one or more support apertures **810** for connecting multi-terminal **602B** to the base plate **400A**.

(98) Reference is now made to FIG. **9B**, which shows a top perspective view of an example three connector multi-terminal **603B** according to examples of the present subject matter. Three connector multi-terminal **603B** may include a first terminal connector **606A**, a second terminal connector **606B**, and a third terminal connector **606C**. Three connector multi-terminal **603B** may also include a plurality of support members **708** and one or more support apertures **810** for connecting multi-terminal **603B** to the base plate **400**.

(99) Four connector multi-terminals **604**, or N-connector multi-terminals, may also include one or more support members **708** and one or more support apertures **810** for connecting to the base plate **400A**.

(100) FIG. **10** shows an example of a multi-terminal **600** according to examples of the present subject matter.

(101) Reference is now made to FIG. **10**, which shows a bottom perspective view of an example three connector multi-terminal **603B** according to examples of the present subject matter. Three connector multi-terminal **603B** may include a first terminal connector **606A**, a second terminal connector **606B**, and a third terminal connector **606C**. Three connector multi-terminal **603B** may also include a plurality of support members **708** and one or more support apertures **810** for

connecting multi-terminal **603B** to the base plate **400**.

(102) The first terminal connector **606A** may include an aperture **610A** for electromechanically connecting the multi-terminal **603B** to one or more other elements of the electrical supply system **100** (e.g., a backup interface module **300A**, a different multi-terminal **600**, a power source **102**, one or more load groups **112**, etc.). For example, the one or more other elements of the electrical supply system **100** may be connected to terminal connector **606A** with a fastening element **608A** to secure the connection between them. The fastening element **608A** may be disposed inside aperture **610A**. For example, the fastening element **608A** may be a screw, bolt, plug, etc. As an example, a conducting (e.g., metallic) busbar may be disposed in physical connection with the multi-terminal **603B** and the busbar may be secured to the multi-terminal **603B** by connecting the fastening element **608A** to the terminal connector **606A** (e.g., by threading the screw through an aperture in the busbar and tightening the screw within aperture **610A** of the terminal connector **606A**). As an example, the busbar may be part of an electromechanical connector **302** of the backup interface module **300A**. The busbar may connect to the electrical circuitry of the backup interface module **300A** and/or a jumper for connecting the multi-terminal **603B** to another multi-terminal **600**. By electromechanically connecting the multi-terminal **603B** to one or more other elements of the electrical supply system **100** using a relatively good conducting fastening element **608A** (e.g., a metallic screw), relatively high currents may be passed with a relatively lower risk of causing a problem (e.g., due to the relatively high currents or a relatively high voltage typically associated with relatively high currents) compared to other fastening elements (such as, fastening elements that include plastic).

(103) The second terminal connector **606B** may include a first aperture **610B** and a second aperture **612B** for connecting the multi-terminal **603B** to one or more other elements of the electrical supply system **100**. For example, the connecting the multi-terminal **603B** to one or more other elements of the electrical supply system **100** may be connected to terminal connector **606B** with a fastening element **608B**. For example, the fastening element **608B** may be disposed inside aperture **610B**. For example, the fastening element **608B** may be a screw, bolt, plug, etc. For example, the second aperture **612B** may be substantially perpendicular to the first aperture **610B**. The second aperture **612B** may be arranged to facilitate electrical contact between an electrical conductor (such as a jumper) placed in the second aperture **612B** and an electricity conducting element of the multi-terminal **603B**. For example, the second aperture **612B** may be arranged to facilitate the electrical contact between an electrical conductor placed in the second aperture **612B** and a fastening element **608A** placed in the aperture **610A** of the first terminal connector **606A**. As an example, a conducting (e.g., metallic) electrical conductor (e.g., jumper) from one or more other elements of the electrical supply system **100** may be disposed in physical connection with the multi-terminal **603B** and the electrical conductor (e.g., jumper) may be secured to the multi-terminal **603B** by connecting the fastening element **608B** to the terminal connector **606B** (e.g., by threading the wire through the aperture **612B** in the multi-terminal **603B** and tightening the screw within aperture **610B** of the terminal connector **606B**). The electrical conductor (e.g., an end of the wire) may be placed in electrical contact with a fastening element **608A** placed in the aperture **610A** of the first terminal connector **606A** before the fastening element **608B** is tightened to secure the electrical conductor to the multi-terminal **603B**.

(104) The third terminal connector **606C** may include a first aperture **610C**, a second aperture **612C**, and a third aperture **614C** for connecting the multi-terminal **603B** to one or more other elements of the electrical supply system **100**. For example, the one or more other elements of the electrical supply system **100** may be connected to terminal connector **606C** with a fastening element **608C**. For example, the fastening element **608C** may be disposed inside aperture **610C**. For example, the fastening element **608C** may be a screw, bolt, plug, etc. For example, the second aperture **612C** may be substantially perpendicular to the first aperture **610C**. For example, the third aperture **614C** may be substantially parallel to the first aperture **610C** and substantially

perpendicular to the second aperture **612C**. The first aperture **610C**, second aperture **612C**, and third aperture **614C** may together form a “T-shaped” aperture of third terminal connector **606C**. The second aperture **612C** and the third aperture **614C** may be arranged to facilitate electrical contact between an electrical conductor (e.g., a wire or cable) placed in the second aperture **612B** and an electricity conducting element of the multi-terminal **603B**. For example, the third aperture **614C** may be arranged to facilitate electrical contact between an electrical conductor placed in the second aperture **612B** and another electrical conductor from one or more other elements of the electrical supply system **100** that is placed in the aperture **612B** of the second terminal connector **606B**. As an example, a conducting (e.g., metallic) electrical conductor (e.g., jumper) from one or more other elements of the electrical supply system **100** may be disposed in physical connection with the multi-terminal **603B** and the electrical conductor (e.g., jumper) may be secured to the multi-terminal **603B** by connecting the fastening element **608C** to the terminal connector **606C** (e.g., by threading the wire through the second aperture **612C** and the third aperture **614C** in the multi-terminal **603B** and tightening the screw within aperture **610C** of the terminal connector **606C**). The electrical conductor (e.g., an end of the wire) may be placed in electrical contact with a different electrical conductor placed in the aperture **612B** of the second terminal connector **606B** before the fastening element **608C** is tightened to secure the electrical conductor placed in terminal connector **606C** to the multi-terminal **603B**.

(105) A similar arrangement may be provided for four connector multi-terminals **604**, or N-connector multi-terminals. The fourth or N terminal connectors may each have a plurality of apertures **610**, **612**, and **614**, which may form a “T-shaped” aperture and a respective fastening elements **608**.

(106) FIG. **11** shows an example of a multi-terminal **600** according to examples of the present subject matter.

(107) Reference is now made to FIG. **11**, which shows a bottom view of an example three connector multi-terminal **603B** according to examples of the present subject matter. Three connector multi-terminal **603B** may include a first terminal connector **606A**, a second terminal connector **606B**, and a third terminal connector **606C**. Three connector multi-terminal **603B** may also include a plurality of apertures **610**, **612**, **614**, and fastening elements **608**.

(108) FIGS. **12A** to **14** show an example of a backup interface enclosure **200B**.

(109) Reference is now made to FIG. **12A**, which shows an example of a backup interface enclosure **200B** which may include a backup interface module **300B** and a base plate **400B**. Backup interface module **300B** may contain electronic circuitry (e.g., one or more relays, detection circuits, power devices, transformers, automatic transfer relays, cooling devices, etc.). Backup interface module **300B** may be mounted to base plate **400B**. Base plate **400B** may be mounted inside an electrical mounting **110**. Base plate **400B** may include a plurality of multi-terminals **600**. Each of the multi-terminals **600** may include a plurality of terminal connectors **606** (as may be shown, for example, in FIGS. **6A** to **11**). The base plate **400B** of FIG. **12A** may have a plurality of two connector multi-terminals **602** and a plurality of three connector multi-terminals **603**. One or more of the multi-terminals **600** may be connected to the backup interface module **300B** via electromechanical connectors **302** (as may be shown, for example, in FIG. **3A**). A section **1200** of FIG. **12A** is shown in greater detail in FIG. **12B**.

(110) FIG. **12B** shows an example of a section **1200** of a backup interface enclosure **200B**.

(111) Reference is now made to FIG. **12B**, which shows an example of a section **1200** of a backup interface enclosure **200B**. As shown in FIG. **12A** and FIG. **12B**, base plate **400B** may include a plurality of rails **900** that each have an aperture **902** formed by a pair of rail members **904**. One or more multi-terminals **600** with a single support member **708** or a plurality of support members **708** (as may be shown as multi-terminals **602B** and **603B**) may be secured to base plate **400B** by connecting the plurality of support members **708** to the plurality of rails **900** by placing each support member **708** into a corresponding aperture **902**. In some examples, there may be N support



members **708** and N corresponding apertures **902**, where N is any appropriate number. Each pair of support members **708** may form a support aperture **810**.

(112) In the example of FIG. **12B**, base plate **400B** may include a first rail **900A** that has a first aperture **902A** formed by a first pair of rail members **904A** and a second rail **900B** that has a second aperture **902B** formed by a second pair of rail members **904B**. One or more multi-terminals **600** with a single support member **708** (as may be shown as multi-terminals **602A**) may be secured to base plate **400B** by connecting a support member **708** (as may be shown, for example, in FIG. **3A**) to the first rail **900A** (e.g., placing the support member **708** into the first aperture **902A**). One or more multi-terminals **600** with a plurality of support members **708** (shown as multi-terminals **602B**, **603B**) may be secured to base plate **400B** by connecting a first support member **708** to the first rail **900A** by placing the first support member **708** into the first aperture **902A** and connecting a second support member **708** to the second rail **900B** by placing the second support member **708** into the second aperture **902B**. For example, when multi-terminals **602B**, **603B** are connected to the base plate **400A**, one or more rail members **904** of the plurality of rails **900** may be placed into support aperture **810**. The plurality of support members **708** and the one or more support apertures **810** may provide additional stability to the connection of the multi-terminal **602B**, **603B** to the base plate **400B**. One or more multi-terminals **600** with a single support member **708** may be secured to base plate **400B** by connecting a support member **708** to the second rail **900B** (e.g., placing the support member **708** into the second aperture **902B**).

(113) FIG. **13** shows a top perspective view of the backup interface enclosure **200B**.

(114) FIG. **13** shows a perspective view of a backup interface module **300B** electromechanically connected to base plate **400B** using one or more fastening elements **608**. Fastening elements **608** may be arranged to electromechanically connect one or more electromechanical connectors **302** to one or more multi-terminals **600** when the backup interface module **300B** is aligned with the base plate **400B**. For example, one or more protuberances **308** of the backup interface module **300B** may be accepted by one or more curved tracks **500** of the base plate **400B** to form a hinged connection between the backup interface module **300B** and the base plate **400B**. When the one or more protuberances **308** are received at or near the end of the curved track **500**, the one or more electromechanical connectors **302** may be aligned with one or more terminal connectors **606** of the one or more multi-terminals **600**.

(115) FIG. **14** shows a side view of the backup interface enclosure **200B**.

(116) FIG. **14** shows a side view of an electromechanical connector **302** of the backup interface module **300B** that may be connected to a corresponding terminal connector **606** of a multi-terminal **600** of the base plate **400B** using a fastening element **608**. Electromechanical connector **302** of the backup interface module **300B** may be aligned with the corresponding terminal connector **606** of the multi-terminal **600** of the base plate **400B** due to the arrangement of one or more protuberances **308** of the backup interface module **300B** inside one or more corresponding curved tracks **500** of the base plate **400B**. For example, placing the one or more protuberances **308** at the end of the corresponding curved tracks **500** may align an aperture of the one or more electromechanical connectors **302** with an aperture of the one or more corresponding terminal connectors **606**. The backup interface module **300B** may be electromechanically connected to the base plate **400B** by securing one or more fastening elements **608** inside the corresponding aligned apertures of the one or more electromechanical connectors **302** and the one or more terminal connectors **606**. As an example, a screw, bolt, plug, etc. may be placed inside each of one or more of the corresponding apertures to fasten the backup interface module **300B** to the base plate **400B**.

(117) Placing the one or more protuberances **308** at the end of the corresponding curved tracks **500** to align the one or more electromechanical connectors **302** with the one or more corresponding terminal connectors **606** may also result in the back cover **306** of the backup interface module **300B** to rest against a front surface of the base plate **400B**. For example, one or more heat dispersing elements **304** of the back cover **306** may be placed in contact with the surface of the

base plate **400B**. Back cover **306** may be arranged to house and protect elements (e.g., circuitry) located inside the backup interface module **300B**.

(118) FIGS. **15** and **16** show examples of backup interface enclosures **200C** and **200D** with their front cover **305** removed.

(119) Reference is now made to FIG. **15**, which shows an example of a backup interface enclosure **200C** with the front cover **305** of the backup interface module **300C** removed. Backup interface module **300C** may include one or more jumpers **1500** housed inside the walls of the housing of the backup interface module **300C**. Each jumper **1500** may include a first leg **15A** and a second leg **15B**. The legs **15A** and **15B** of the jumpers may be the electromechanical connectors **302** (e.g., lugs) of the backup interface module **300C** used to connect the backup interface module **300C** to the multi-terminals **600** of the base plate **400B**. Each leg **15A** or **15B** may include an aperture for connecting the jumper **1500** to a plurality of multi-terminals **600**. For example, a first jumper **1500** may be connected to multi-terminal **603BA** and multi-terminal **603BB**. A second jumper **1500** may be connected to multi-terminal **603BC** and multi-terminal **603BD**. For example, the jumper **1500** may be connected to each terminal connector **606A** with a fastening element **608A**. As an example, the jumper **1500** may be a conducting (e.g., metallic) busbar with a first leg **15A** and a second leg **15B**, with each having a respective aperture for connecting to a corresponding multi-terminal **600**. The first leg **15A** of the busbar may be disposed in physical contact with the first multi-terminal **603BA** and the second leg **15B** of the busbar may be disposed in physical contact with the second multi-terminal **603BB**. The busbar may be secured to the first multi-terminal **603BA** by connecting a first fastening element **608A** to the first terminal connector **606A** of the first multi-terminal **603BA** and a second fastening element **608A** to the first terminal connector **606A** of second multi-terminal **603BB** (e.g., by threading the first screw **608A** through the aperture in the first leg **15A** and tightening the first screw **608A** within aperture **610A** of the terminal connector **606A** of the first multi-terminal **603BA**, and threading the second screw **608A** through the aperture in the second leg **15B** and tightening the screw **608A** within aperture **610A** of the terminal connector **606A** of second multi-terminal **603BB**). By electromechanically connecting the backup interface module **300C** to the multi-terminals **600** of the base plate **400B** using a relatively good conducting fastening element **608A** (such as, a metallic screw), relatively high currents may be passed with a relatively lower risk of causing a problem (e.g., due to the relatively high currents or a relatively high voltage typically associated with relatively high currents) compared to other fastening elements (such as, fastening elements that include plastic).

(120) Reference is now made to FIG. **16**, which shows an example of a backup interface enclosure **200D** with the front cover **305** of the backup interface module **300D** removed. Backup interface module **300D** may include electronic circuitry **1600** housed inside the walls of the housing of the backup interface module **300D**. Electronic circuitry **1600** may include: one or more relays, detection circuits, power devices, transformers, automatic transfer relays, cooling devices, etc. Electronic circuitry **1600** may be connected to multi-terminals **600** using electromechanical connectors **302**. For example, each of the electromechanical connectors **302** may be connected to a terminal connector **606A** with a fastening element **608A**. As an example, each electromechanical connector **302** may be a conducting (e.g., metallic) busbar having at least one aperture for connecting to a respective multi-terminal **600** of the base plate **400B**. The electromechanical connector **302** may be a busbar that connects to the electronic circuitry **1600** housed inside the walls of the housing of the backup interface module **300C**. Each busbar may be disposed in physical contact with a respective multi-terminal **600** and each busbar may be secured to the respective multi-terminal **600** by connecting a fastening element **608A** to the terminal connector **606A** (e.g., by threading the screw through the aperture **610A** and tightening the screw within aperture **610A** of the terminal connector **606A**). By electromechanically connecting the backup interface module **300D** to the multi-terminals **600** of the base plate **400B** using a relatively good conducting fastening element **608A** (such as, a metallic screw), relatively high currents may be

passed with a relatively lower risk of causing a problem (e.g., due to the relatively high currents or a relatively high voltage typically associated with relatively high currents) compared to other fastening elements (such as, fastening elements that include plastic).

(121) Each electromechanical connector **302** may include an additional aperture and fastening element **608** on the other side of metallic busbar housed inside the backup interface module **300D** to connect the electromechanical connector **302** to electronic circuitry **1600**. This arrangement may connect the backup interface module **300D** to one or more other elements of the electrical supply system **100** via the multi-terminals **600** of the base plate **400B**.

(122) Different backup interface modules **300** may allow for modularity. For example, depending on whether full backup, partial backup, or no backup is to be arranged, different backup interface modules **300** may be connected to the base plate **400A** and/or base plate **400B**. For example, if no backup is to be arranged, then backup interface module **300C** may be connected to base plate **400B**. If full backup or partial backup is to be arranged, then backup interface module **300D** may be connected to base plate **400B**. The different backup interface modules **300** may be connected for different situations. After one type of backup interface module **300** has been connected, it may be replaced by a different backup interface module **300**. For example, if at first no backup is arranged, but then full backup or partial backup is to be arranged, then backup interface module **300C** may be switched with backup interface module **300D**.

(123) In residential applications, photovoltaic (PV) systems are available to provide limited auxiliary power, which may be, in some cases, less power than a utility grid. In some cases, a battery or other energy storage device might provide limited backup power and energy. Thus, it may be advantageous to provide means for allocating the reduced power to only the critical loads during a backup mode of operation. The installation of typical residential PV systems may be enhanced by a separate back-up panel for the critical loads, so that critical loads are connected to the separate back-up panel when the backup power source is providing power to the back-up panel.

(124) Reference is now made to FIG. **17A**. A backup system comprises a base plate **400C** (e.g., base plate **400A**, base plate **400B**). In FIG. **17A**, dotted arrows **115** are intended to indicate a mechanical connection. Due to the limits of depiction in the figures, a depiction of the actual connection is not provided. The base plate **400C** may comprise a plurality (e.g., as shown in FIG. **17A**, three) multi-terminals **600C** (e.g., multi-terminals **600**, multi-terminals **600A**, multi-terminals **600B**). Each multi-terminal **600C** of the multi-terminals **600C** may comprise a plurality of terminal connections **140** (e.g., using one or more terminal connectors **606**). Each terminal connection **140** of the plurality of terminal connections **140** may be mechanically and electrically configured to connect to a terminal of a power source (e.g., a primary power source **150**), a load group **112**, or a second of the multi-terminals **600C**. Each multi-terminal **600C** of the plurality of multi-terminals **600C** may include two or more sets of terminal connections **140**—for example, positive and negative connections in case of direct current power, or Line-1 and Line-2 (and, in some cases, Line-3 for three-phase power, and/or a neutral line connection) connections in case of alternating current power.

(125) A first load group **112C** may be electrically connected to one of the terminal connections **140** in a first one of the multi-terminals **600C**. A second load group **112D** may be electrically connected to one of the terminal connections **140** in a second one of the multi-terminals **600C**. According to some features, the base plate **400C** may be configured to be mounted next to or as part of an electrical distribution panel **120**, such as a mounting **110** of FIG. **1**, and may share a common enclosure with electrical distribution panel **120** (e.g., electrical distribution panel **120** and base plate **400C** may be disposed in a common electrical cabinet). For example, first and second load groups **112C** and **112D** may be connected (e.g., via circuit breakers) to electrical distribution panel **120**. The electrical distribution panel **120** may include circuit breakers and/or other circuitry configured to connect to electrical loads. Individual loads of first load group **112C** may be connected to multi-terminals **600C** via electrical distribution panel **120**, and individual loads of second load group

**112D** may be connected to multi-terminals **600C** via another electrical distribution panel. For simplicity, figures in the disclosure herein depict a direct connection between load groups **112C** and **112D** and multi-terminals **600C**, but it is to be understood that a physical connection between loads of a load group and multi-terminals **600C** may include a physical connection via an electrical distribution panel.

(126) A first jumper **170A** may provide an electrical connection between a first one of the multi-terminals **600C** and a second one of the multi-terminals **600C**. A second jumper **170B** may connect the second one of the multi-terminals **600C** and a third one of the multi-terminals **600C**. A third jumper **170C** may connect the third one of the multi-terminals **600C** and a fourth one of the multi-terminals **600C**. The fourth one of the multi-terminals **600C** may be connected to the power source **150**. The power source **150** may be a main electrical grid and may provide an AC electricity output to the first load group **112C** and the second load group **112D**, via the multi-terminals **600C** and the jumpers **170A**, **170B**, **170C**.

(127) Jumpers **170A**, **170B**, and/or **170C** (as well as other jumpers described herein) may each comprise a length of an electrical conductor (e.g., aluminum or copper) used to close, open or bypass part of an electronic circuit. It is appreciated that the terms “closed” or “on” may be used interchangeably to refer to a configuration where the jumper is physically connected between two terminal connections **140** disposed in different or the same multi-terminal **600C**.

(128) The above discussion is by way of example and not meant to be limiting. For example, there may be three, five, or even ten of the multi-terminals **600C**. The multi-terminals **600C** are depicted as having four-terminal connections **140**, however, any number of terminals is possible. Further, each multi-terminal **600C** may have one or more instances or pairs (e.g., for positive and negative connections, or multi-line or multi-phase connections, and/or to provide a neutral line).

(129) The mechanical connection indicated by the dotted arrows **115** in FIG. **17A** may, for example, comprise a hanging track (not depicted), into which a protuberance, tab, rod, dowel, or other matching mechanical connectors of the backup interface module **120A** may be inserted.

(130) The combination of the multi-terminals (such as **600** and similar references) on the base plate (such as base plate **400** and similar references), a hinged backup interface (such as **200**, **300**, or similar references) containing relays (such as **210**, **310**, **510** and similar references), and jumpers (e.g., jumpers **1500**, **170A**, **170B**, **170C**, **270A**, **270B**, **370A**, **370B**, and **570B**) allows configuring the electrical partial or full house electrical backup according to the end-user requirements or needs. When the end-user wishes to reconfigure the partial or full house electrical backup, the reconfiguration and/or changes may be implemented with little disruption and downtime to the electrical system of the residence. For example, switching from a partial to a full house backup can be configured by replacing the hinged backup interface and jumpers on the multi-terminals. For example, changing loads in a partial house backup from a critical load group to a non-critical load group can be configured by switching a jumper on the multi-terminals. For example, changing a partial house backup from two load groups to three load groups, such as connecting one load group to solar power when available, connecting another load group to a battery backup, and a third (non-critical) load group to the utility grid, may be configured by replacing the hinged backup interface, reconfiguring the jumpers, and/or switching the load between the groups. Using the multi-terminals, base plate, hinged backup interface containing relays, and the jumpers solves the problem of configuring a partial or full house backup to residential or other types of power generation and storage capabilities, and enables efficient reconfiguration of the different load groups to meet the end-user usage needs and residential capabilities when the capabilities are updated.

(131) Reference is now made to FIG. **17B**, which shows a backup interface module **300E** disposed in the base plate **400C**. Backup interface module **300E** may be a cover, and may comprise jumpers configured to connect multi-terminals **600C** to one another, instead of using jumpers **170A-170C** depicted in FIG. **17A**. Providing backup interface module **300E** may simplify and reduce

installation-time, by enabling quick and easy interconnection of multi-terminals. Backup interface module **300E** may be designed in a modular manner, such that it may be of a similar or identical mechanical design as a backup interface module, and may be removed and replaced with a backup interface module including active circuitry, if backup capability is to be added to the system.

(132) Reference is now made to FIG. **18A**, which shows an example wiring configuration of the backup system. A backup interface module **300F** may be configured to be connected to (e.g., disposed in or placed on) the base plate **400C**. The backup interface module **300F** may comprise active circuitry which is connected to multi-terminals **600C** when the backup interface module **300E** is connected to base plate **400C**. By way of example, a relay **210** may be comprised in the backup interface module **300E**. The relay **210** may comprise, for example, an electromechanical relay, a solid state relay (e.g., MOSFETs, IGBTs, other transistors).

(133) The relay **210** may comprise a switching mechanism connected (when the backup interface module is placed on the base plate) between two or more of the multi-terminals **600C**. A first load group **112C** may be connected (e.g., electrically connected) to a first one of the multi-terminals **600C**. The first load group **112C** may be connected to an alternative power source **170**, such as a photovoltaic inverter, which may convert power from photovoltaic modules (e.g., panels or shingles) to AC power. Alternative power source **170** may also be referred to as “alternate power source” or “backup power source”. A second load group **112D** may be connected (e.g., electrically connected) to a second one of the multi-terminals **600C**, which may, in turn, be connected via jumpers **270A** and **270B** to power source **150**, which may be a primary power source, such as a local utility electrical grid. The relay **210** may be normally closed, such that alternative power source **170**, load groups **112C** and **112D** and power source **150** are all interconnected. Relay **210** may be opened (e.g., turned off) in the event of an outage (e.g., a power failure) of the power source **150**. In such a case, the first load group **112C** may not be powered by power source **150**. Rather, first load group **112C** may be powered by alternative power source **170**, while galvanic isolation between alternative power source **170** and power source **150** may be provided by relay **210** being open. Galvanic isolation between alternative power source **170** and power source **150** may allow technicians to operate for the resumption of power from power source **150** without danger of being electrocuted by power produced by alternative power source **170**.

(134) The first one of the multi-terminals **600C** and the second one of the multi-terminals **600C** may be connected by the relay **210**, which may comprise a power relay. The relay **210** may, for example, comprise an electromechanical relay or (where this may be permitted by local regulations) a solid-state relay (e.g., MOSFETs, IGBTs, or other transistors).

(135) In the configuration of FIG. **18A**, the alternative power source **170** may provide backup power to the first load group **112C** when the relay **210** is open.

(136) Reference is now made to FIG. **18B**, which shows an example wiring configuration of the backup system. In the example wiring configuration of FIG. **18B**, a first multi-terminal **600C** is connected to power source **150** (e.g., an electrical grid), a second multi-terminal **600C** is connected to first load group **112C**, a third multi-terminal **600C** is connected to second load group **112D**, and a fourth multi-terminal **600C** is connected to alternative power source **170**. Backup interface module **300F** comprises a first relay **210A** connected between the fourth and third multi-terminals, a second relay **210B** connected between the third and second multi-terminals, and a third relay **210C** connected between the second and first multi-terminals. When all three relays are closed (e.g., turned on), all four multi-terminals may be interconnected. Such as when power source **150** is not able to provide power (e.g., due to grid outage), relay **210C** may be opened, which may isolate power source **150** (e.g., for the safety of personnel that may access power source **150**). According to a first backup configuration, relays **210B** and **210A** may be closed (e.g., turned on), connecting loads groups **112C** and **112D** to alternative power source **170**. According to a second backup configuration, relay **210A** may be closed (e.g., turned on), connecting loads groups **112C** to alternative power source **170**, while relay **210B** is open (e.g., turned off), disconnecting load group

**112D** from alternative power source **170**. The second configuration may be preferable when alternative power source **170** does not produce enough power to power both loads groups **112C** and **112D**, and load group **112C** may comprise critical loads.

(137) A controller (not explicitly depicted, but connected to the circuitry of backup interface module **300F**) may be configured to always select either the first or second backup configurations in case of a backup condition, or may selectively choose either the first or second backup configuration based on current power production capabilities of alternative power source **170**, power drawn by loads groups **112C** and **112D**, and/or the like. The selective choosing may be based on sensor(s) measurements, and or communication signals received by the controller.

(138) Reference is now made to FIG. **19A**, which shows an example wiring configuration of the backup system. Relay **310** of backup interface module **300G** may, when closed, connect between the second one of the multi-terminals **600C** and the third one of the multi-terminals **600C**. The first one of the multi-terminals **600C** and the second one of the multi-terminals **600C** may be connected by first jumper **370A**. The third one of the multi-terminals **600C** and the fourth one of the multi-terminals **600C** may be connected by second jumper **370B**.

(139) In the event of a failure of the alternative power source **150**, backup power may be provided by alternative power source **170** to the first load group **112C** and the second load group **112D** via first jumper **370A**. In such a case, the relay **310** may be open (e.g., turned off). The configuration of FIG. **19A** may provide reduced flexibility compared to the configuration of FIG. **18B**, but may provide a reduced component count and simpler control.

(140) Reference is now made to FIG. **19B**, which shows an example wiring configuration of the backup system. In the configuration of FIG. **19B**, relay **310B** of backup interface module **300H** may comprise a multiple switching circuit relay (similar to or the same as two or more of the three relays shown in FIG. **18B**). In the configuration of FIG. **19B**, Relay **310B** may connect the first of the multi-terminals **600C**, to which the power source **150** is electrically connected, to the third and fourth ones of the multi-terminals **600C**. Accordingly, power may be provided to the second load group **112D** from the power source **150** via two closed switches of Relay **310B**, creating an electrical connection between the power source **150** and the second load group **112D** over the first and third of the multi-terminals **600C**. In the event of a failure of power source **150**, a third switch of the Relay **310B** may close, electrically connecting load group **112D** to alternative power source **170**.

(141) Relay **310B** may comprise an automatic transfer switch (ATS). The ATS may include interlock functionality. For example, Relay **310B** may include switching circuitry and a controller configured to selectively connect a multi-terminal connected to load group **112D** to either a multi-terminal connected to alternative power source **170**, or to a multi-terminal connected to power source **150**, but never both at once. The interlock functionality may be electrical. For example, such as by providing a first signal to a first relay contact connecting load group **112D** to a multi-terminal connected to alternative power source **170**, and a second signal that is an inversion of the first signal to a second relay contact connecting load group **112D** to a multi-terminal connected to power source **150**. In this manner, a connection between alternative power source **170** and power source **150** may be made or broken by operating a third relay contact independently of the first and second relay contacts. This may help reduce the chance of an accidental connection between alternative power source **170** and power source **150** via the load group multi-terminals.

(142) Reference is now made to FIG. **20**, which shows an example connection between a base plate **400D** and a backup interface module having electronics **300J**. The base plate **400D** may be the same as or similar to the base plate **400C** of FIG. **17**, or other base plates **400** shown and described herein. The base plate **400D** may be affixed to the backup interface module with electronics **300J**. The base plate **400D** may comprise two connection points **430A** and **430B**. The backup interface module with electronics **300J** may comprise two connection points **420A** and **420B**. When the backup interface module with electronics **300J** is inverted (as indicated by the dotted arrows), the

connection point **420A** of module **300J** is substantially aligned with the connection point **430A** of base plate **400D**, and the connection point **420B** of module **300J** is substantially aligned with the connection point **430B** of base plate **400D**. When the connection points **420A** and **420B** are aligned with the connection point **430A** and **430B** (respectively), the mechanical connection indicated by the dotted arrows **115A** in FIG. **17B** may then be formed by inserting the connection point **430A** into backup interface module with the connection point **420A** and the connection point **430B** into the connection point **420B**.

(143) Connection points **420A-430A** and **420B-430B** may form, for example, a hinged attachment. The hinged attachment may be a fixed hinged attachment, or may be a removable hinge.

Appropriate hinge attachment mechanisms may be used to provide the connection at connection points **420A-430A** and **420B-430B**. For example, the hinge may include one or more protuberances of the backup interface module and one or more curved tracks of the base plate.

(144) The backup interface module with electronics **300J** may comprise various connection elements **430A**, **430B**, **430C**, **430D**, and **430E**, (by way of a non-limiting example, five such elements are depicted, but any number are possible). The number of such connection elements **430A**, **430B**, **430C**, **430D**, and **430E** may vary as needed, depending on a given implementation. Connection elements **430A**, **430B**, **430C**, **430D**, and **430E** may comprise protrusions, screws, rivets, bolts, or other fastener elements. These may allow for connections **440** to mate with corresponding terminal connections **140**. When the backup interface module with electronics **420** is attached to the base plate, the connection elements **430A**, **430B**, **430C**, **430D**, and **430E** may align with and penetrate into a corresponding one of the plurality of terminal connections **140** comprised in the multi-terminals **600C**. In such a fashion, the electronics in the backup interface module with electronics **420** may be connected. The various connection elements **430A**, **430B**, **430C**, **430D**, and **430E** may include one or more electromechanical connectors **302** and/or one or more fastening elements **608**.

(145) Selectively connecting or disconnecting any one load group of the plurality of load groups **112C**, **112D**, etc. may be commanded by a controller. For example, operations may be controlled based on a sensor reading indicating a failure of the power source **150**, or based on a communication received by a communication device coupled to the controller. The controller may comprise an appropriate computing device comprising one or more microprocessors, microcontrollers, analog control circuits, or other appropriate computing devices.

(146) The controller may provide an execution platform for executing machine readable instructions such as software. One of the one or more microprocessors, microcontrollers may be a special purpose processor operative for executing the operations of the controller as described herein.

(147) The controller may, by controlling the at least one power relay and other switches which may be present in the device backup interface module **300**, selectively provide backup power to one or more load groups **112**.

(148) For example, if a first load group comprises a heating unit, a second load group comprises a television, and a third load group comprises a refrigerator, the apparatus described herein may be configured to provide electrical power to the refrigerator under all circumstances, while the heating unit may be selectively powered, depending on seasonal concerns (e.g., time of year). Additionally or alternatively, the apparatus may be configured to not provide power to the television, for example, during a power outage.

(149) Additionally or alternatively, the apparatus may be configured to provide power to the refrigerator and the heating unit under all circumstances, while only providing power to the television if enough power may be provided to the refrigerator and the heating unit for a minimum of a period of time (e.g., 4 hours).

(150) It is appreciated that such configuration may be performed manually by physically connecting the load group(s) with jumpers, as may be described above for example with reference

to FIGS. **17A** and **19A**. Alternatively, by using switching mechanisms (e.g., the relays **210**, **210A-C**, **310**, **310B**), which may be controlled by the controller, the load center may have its electrical power needs supplied via the second section and at a later stage, via the first section.

(151) The alternative power source **170** may, by way of example, comprise a photovoltaic inverter that is attached to a photovoltaic (PV) system. The inverter may convert DC electricity provided by a plurality of PV panels into AC electricity, which is then provided to an AC electric grid, which may, by way of example, be the community electric power grid. The PV system may also provide DC power to a battery, which may also be connected to one of the plurality of terminal connections **140**. Accordingly, in the event of a failure of the local electric power grid, the battery may serve as an additional source of electrical power. In some cases, a battery may be coupled to a second inverter having an AC output connected to the AC output of the photovoltaic inverter. Various load groups **112** may be assigned priorities which the controller uses to determine which of the various load centers is to be provided electrical power at the expense of which other of the various load centers. For example, if the heating unit, the refrigerator, and the television comprise the various load groups **112**, the controller may be programmed and/or configured to provide electrical power to the heating unit and the refrigerator at the cost of removing electrical power from the television. If the local electrical grid does not return to provide power, the heating unit may be maintained at the cost of removing electrical power from the refrigerator.

(152) In the event of a power failure, a local power source, such as a local electrical power grid, will no longer provide electrical power. The power source, or any additional source of electrical power (for example, a battery), may provide or continue to provide electrical power. If the inverter receives DC electricity from a PV system, as shade increases, or as night falls, a quantity of electricity produced by the PV system may decline or a quantity of stored electricity in the battery may decline. Accordingly, the various load centers, as described above, may be disconnected according to priorities, such as described immediately above. Similarly, as power begins to return to the inverter at daybreak, one of the various load groups **112** may be prioritized for receiving electrical power, while a second one of the load groups **112** may remain without power.

(153) Reference is now made to FIG. **21**, which shows an example wiring configuration of the backup system apparatus. Alternative power source **170**, first and second load groups **112C** and **112D**, and power source (e.g., utility grid) **150** may be connected (such as may be shown in FIG. **18B**). Relays **510A** and **510B** may be the same as or similar to relays **210A** and **210B** of FIG. **18B**. In the example of FIG. **21**, power source **150** may be directly connected to load group **112D** via a jumper **570B** such that in case of an outage of power source **150**, load group **112D** cannot be backed up while maintaining isolation from power source **150**.

(154) Backup interface module **300K** may further include transformer **512**. Transformer **512** may be connected to alternative power source **170** via relay **510A** and a multi-terminal **600C**, and may be configured to provide a split-phase voltage. For example, if power source **150** provides a split-phase grid voltage (e.g., two phases of about 110V or about 120V each) under normal operating conditions, relay **510C** may be open (e.g., turned off) as long as power source **150** is connected to the system. If power source **150** is disconnected, transformer **512** may convert a voltage output of about 220V or about 240V provided by alternative power source **170** to two 110V or 120V split-phase outputs, such that the two 110/120V split phase outputs may be provided to load group **112C**. In cases where load group **112D** may also be backed up (e.g., in the system of FIG. **18B** or **19B**), the transformer **512** may also provide a split phase output to load group **112C**. Transformer **512** may include three taps—two taps for receiving the 220/240V output of alternative power source **170**, and a third, midpoint voltage tap for providing the split phase outputs.

(155) Although examples are described above, features and/or steps of those examples may be combined, divided, omitted, rearranged, revised, and/or augmented in any desired manner. Various alterations, modifications, and improvements will readily occur to those skilled in the art. Such alterations, modifications, and improvements are intended to be part of this description, though not



expressly stated herein, and are intended to be within the spirit and scope of the disclosure. Accordingly, the foregoing description is by way of example only, and is not limiting.

#### Clauses

(156) Clause 1: A base plate comprising: a frame; at least three multi-terminals, wherein each multi-terminal of the at least three multi-terminals comprises two or more terminal connectors; and at least one curved track.

(157) Clause 2: The base plate of clause 1, wherein at least one terminal connector of the two or more terminal connectors is configured to electrically connect to a power device.

(158) Clause 3: The base plate of any one of the preceding clauses, wherein at least one terminal connector of the two or more terminal connectors is configured to mechanically connect to a power device.

(159) Clause 4: The base plate of any one of the preceding clauses, wherein at least one terminal connector of the two or more terminal connectors is configured to connect to a power source.

(160) Clause 5: The base plate of any one of the preceding clauses, wherein at least one terminal connector of the two or more terminal connectors is configured to connect to a load group.

(161) Clause 6: The base plate of any one of the preceding clauses, wherein at least one terminal connector of the two or more terminal connectors is configured to connect to at least one other terminal connector of a different one of the at least three multi-terminals.

(162) Clause 7: The base plate of any one of the preceding clauses, wherein at least one multi-terminal of the at least three multi-terminals comprises three terminal connectors.

(163) Clause 8: The base plate of any one of the preceding clauses, wherein the at least one curved track is C-shaped.

(164) Clause 9: The base plate of any of the preceding clauses, wherein the frame is configured to mechanically connect to a mounting.

(165) Clause 10: The base plate of clause 9, wherein the mounting comprises an electrical distribution panel.

(166) Clause 11: The base plate of any one of clauses 1 to 7, wherein the at least one curved track is J-shaped.

(167) Clause 12: The base plate of any one of the preceding clauses, wherein the at least one curved track is configured to accept a protuberance of a cover.

(168) Clause 13: The base plate of clause 12, wherein the at least one curved track is configured to align an electromechanical connector of the cover with at least one multi-terminal of the multi-terminals of the base plate.

(169) Clause 14: The base plate of clause 13, wherein the electromechanical connector is configured to be secured to the at least one multi-terminal of the multi-terminals of the base plate using at least one fastening element.

(170) Clause 15: An apparatus for a backup interface comprising: at least one electrical circuit; a back cover; at least one protuberance; and at least three electromechanical connectors.

(171) Clause 16: The apparatus of clause 15, wherein the back cover comprises at least one fin.

(172) Clause 17: The apparatus of clause 16, wherein the at least one fin is configured to provide mechanical stiffness to the back cover.

(173) Clause 18: The apparatus of clause 16, wherein the at least one fin is configured to provide thermal heat dissipation.

(174) Clause 19: The apparatus of clause 16, wherein the at least one protuberance is configured to be accepted by a curved track of a base plate.

(175) Clause 20: The apparatus of clause 19, wherein the curved track is configured to align an electromechanical connector of the back cover with at least one multi-terminal of the base plate.

(176) Clause 21: The apparatus of clause 20, wherein the electromechanical connector is configured to be secured to the at least one multi-terminal of the base plate using at least one fastening element.

(177) Clause 22: A backup interface enclosure comprising: a funnel region of a base plate; a curved central track connected to the funnel region; a curved end track connected to the curved central track; wherein a radius of the curved end track is less than a radius of the curved central track.

(178) Clause 23: The backup interface enclosure of clause 22, wherein the radius of the curved end track is substantially less than the radius of the curved central track.

(179) Clause 24: The backup interface enclosure of clause 22, wherein the radius of the curved end track is at least 10% less than the radius of the curved central track.

(180) Clause 25: The backup interface enclosure of clause 22, wherein the radius of the curved end track is in a range of about 5 mm to about 45 mm.

(181) Clause 26: The backup interface enclosure of clause 22, wherein the radius of the curved central track is in a range of about 20 mm to about 50 mm.

(182) Clause 27: The backup interface enclosure of any one of clause 22 to clause 26, wherein the funnel region is defined by at least one curved edge.

(183) Clause 28: The backup interface enclosure of any one of clauses 22 to 27, wherein the funnel region is defined by two edges.

(184) Clause 29: The backup interface enclosure of clause 28, wherein the two edges are non-parallel edges.

(185) Clause 30: The backup interface enclosure of any one of clauses 28 or clause 29, wherein a distance between the two edges increases as a distance from the curved central track increases.

(186) Clause 31: The backup interface enclosure of any one of clause 22 to clause 29, further comprising at least one protuberance is configured to be accepted by the funnel region, curved central track, and curved end track of the base plate.

(187) Clause 32: The backup interface enclosure of clause 31, wherein the funnel region, curved central track, and curved end track are configured to align an electromechanical connector of the backup interface enclosure with at least one multi-terminal of the base plate.

(188) Clause 33: The backup interface enclosure of clause 32, wherein the electromechanical connector is configured to be secured to the at least one multi-terminal of the base plate using at least one fastening element.

(189) Clause 34: A detachable hinge for a backup interface enclosure comprising: a curved track; and a protuberance.

(190) Clause 35: The detachable hinge of clause 34, wherein the curved track comprises a funnel region.

(191) Clause 36: The detachable hinge of clause 35, wherein the funnel region is connected to a curved central track region.

(192) Clause 37: The detachable hinge of clause 36, wherein the curved central region is connected to a curved end track region.

(193) Clause 38: The detachable hinge of clause 37, wherein a radius of the curved end track region is less than a radius of the curved central track region.

(194) Clause 39: The detachable hinge of clause 38, wherein a radius of the protuberance is less than the radius of the curved central track region.

(195) Clause 40: The detachable hinge of clause 39, wherein the radius of the protuberance is about equal to the radius of the curved end track region.

(196) Clause 41: The detachable hinge of clause 40, wherein the protuberance is configured to rotate along an axis of the protuberance when the protuberance is in proximity to the curved end track region.

(197) Clause 42: The detachable hinge of any one of clause 34 to clause 41, wherein the protuberance is configured to be accepted by the curved track, and the curved track is part of a base plate.

(198) Clause 43: The detachable hinge of clause 42, wherein the curved track is configured to align an electromechanical connector of a cover with a multi-terminal of the base plate.

(199) Clause 44: The detachable hinge of clause 43, wherein the electromechanical connector is configured to be secured to the multi-terminal of the base plate using a fastening element.

(200) Clause 45: A multi-terminal for an interface enclosure comprising: a first terminal connector configured to electrically and mechanically connect to a power device; a second terminal connector configured to connect to a power source or a load group; a third terminal connector configured to connect to at least one other terminal connector of a different multi-terminal.

(201) Clause 46: The multi-terminal of clause 45, wherein the multi-terminal is configured to be connected to a base plate.

(202) Clause 47: The multi-terminal of clause 46, wherein base plate further comprises a curved track.

(203) Clause 48: The multi-terminal of clause 47, wherein at least one protuberance is configured (204) to be accepted by the curved track of the base plate.

(205) Clause 49: The multi-terminal of clause 48, wherein the curved track is configured to align an electromechanical connector of a cover with the multi-terminal.

(206) Clause 50: The multi-terminal of clause 49, wherein the electromechanical connector is configured to be secured to the multi-terminal using at least one fastening element.

(207) Clause 51: An apparatus comprising: a base plate configured to mechanically connect to a backup interface module, wherein the base plate comprises a plurality of multi-terminals each comprising a plurality of terminal connections, and wherein each terminal connection of the plurality of terminal connections is configured to be connected to at least one of: a power source, a load group, or a different terminal connection of the plurality multi-terminals.

(208) Clause 52: The apparatus of clause 51, wherein the base plate is configured to connect the power source to: the load group, and a second load group.

(209) Clause 53: The apparatus of clause 52, wherein the power source is a utility grid.

(210) Clause 54: The apparatus of clause 51, further comprising the backup interface module, wherein the backup interface module is mechanically and electrically configured to connect to the base plate.

(211) Clause 55: The apparatus of clause 54, wherein the backup interface module comprises conductors directly connecting at least two of the plurality of multi-terminals to one another.

(212) Clause 56: The apparatus of clause 51, wherein the backup interface module comprises circuitry electrically configured to connect at least two of the plurality of multi-terminals to the backup interface module.

(213) Clause 57: The apparatus of clause 56, wherein the circuitry comprises at least one relay, and wherein the relay is connected between: a first multi-terminal of the plurality of multi-terminals, and a second multi-terminal of the plurality of multi-terminals.

(214) Clause 58: The apparatus of clause 57, wherein the at least one relay is configured to selectively connect the load group to the power source.

(215) Clause 59: The apparatus of clause 57, wherein the at least one relay is configured to selectively connect the load group to a second load group.

(216) Clause 60: The apparatus of clause 57, wherein the circuitry comprises at least a first relay and a second relay, wherein the first relay is configured to selectively connect the load group to the power source, and wherein the second relay is configured to selectively connect the load group to the power source.

(217) Clause 61: The apparatus of any one of clauses 56-60, wherein the circuitry comprises an automatic transfer switch configured to selectively connect the first multi-terminal to either the second multi-terminal or to a third multi-terminal.

(218) Clause 62: The apparatus of clause 61, wherein the circuitry comprises an interlock configured to prevent the first multi-terminal being concurrently connected to the second multi-terminal and the third multi-terminal.

(219) Clause 63: The apparatus of clause 62, wherein the interlock is an electrical interlock.

(220) Clause 64: The apparatus of clause 63, wherein the electrical interlock is implemented by the automatic transfer switch.

(221) Clause 65: The apparatus of any one of clauses 56-64, wherein the backup interface module further comprises a controller.

(222) Clause 66: The apparatus of any one of clauses 56-65, wherein the controller is configured to control the circuitry.

(223) Clause 67: The apparatus of any one of clauses 56-66, wherein the controller is configured to control the circuitry based on a sensor reading indicating a failure of the power source

(224) Clause 68: The apparatus of any one of clauses 56-67, wherein the controller is configured to control the circuitry based on receiving, via a communication device, a communication message indicating a failure of the power source.

(225) Clause 69: The apparatus of any one of clauses 56-68, wherein the backup interface module further comprises a transformer configured to: receive a grid-level voltage at a first set of winding terminals; and output a split-phase grid voltage at a second set and third set of winding terminals.

(226) Clause 70: The apparatus of clause 69, wherein the grid-level voltage is about 220V-240V, and wherein the split-phase grid voltages are about 110V-120V.

(227) Clause 71: The apparatus of any one of clauses 69-70, wherein during a backup mode of operation, the controller is configured to control the circuitry to connect at least one of the second set and third set of winding terminals to at least one load group.

(228) Clause 72: The apparatus of any one of clauses 51-71, wherein the load group is connected to the base plate via a first electrical distribution panel.

(229) Clause 73: The apparatus of clause 72, wherein the base plate is further configured to be mounted alongside the first electrical distribution panel.

(230) Clause 74: The apparatus of any one of clauses 51-73, wherein a second load group is connected to the base plate via a second electrical distribution panel.

(231) Clause 75: The apparatus of clause 74, wherein the base plate is further configured to be mounted alongside the second electrical distribution panel.

(232) Clause 76: The apparatus of any one of clauses 72-75, wherein the base plate, the first electrical distribution panel and the second electrical distribution panel are arranged inside a single electrical enclosure.

(233) Clause 77: A method comprising: controlling, by a controller, circuitry of a backup interface module connected to: a first group of loads, a second group of loads, a primary power source, and a backup power source, to: connect, based on an availability of power from the primary power source, the primary power source to the first group of loads, the second group of loads, and the backup power source; and based on an outage of the primary power source: disconnect the primary power source from the first group of loads and the second groups of loads; and disconnect the backup power source from the first group of loads, the second group of loads, and the primary power source.

(234) Clause 78: The method of clause 77, wherein disconnecting the primary power source comprises opening a relay.

(235) Clause 79: The method of clause 77, wherein disconnecting the backup power source comprises opening a relay.

(236) Clause 80: The method of any of clauses 77-79, further comprising determining the outage based on sensor measurements indicating an outage of the primary power source.

(237) Clause 81: A method comprising: connecting a first load group to a first multi-terminal of a base plate; connecting a second load group to a second multi-terminal of the base plate; connecting a primary power source to a third multi-terminal of the base plate; connecting an alternative power source to a fourth multi-terminal of the base plate; and selectively connecting a plurality of multi-terminals to one another according to one of a plurality of configurations, wherein a first configuration of the plurality of configurations comprises hard-wiring the first, second, third and

fourth multi-terminals to one another, and wherein a second configuration of the plurality of configurations comprises connecting a backup interface module to the base plate, wherein the backup interface module comprises active circuitry for selectively connecting, by a controller, the first, second, third, and fourth multi-terminals based on an operating condition of the primary power source.

## Claims

1. A base plate comprising: a frame; at least three multi-terminals, wherein each multi-terminal of the at least three multi-terminals comprises two or more terminal connectors, and wherein, in at least one multi-terminal of the at least three multi-terminals, at least one terminal connector of the two or more terminal connectors is configured to connect to a relay in a backup interface mechanically connected to the base plate; and a curved track.
2. The base plate of claim 1, wherein, in the at least one multi-terminal of the at least three multi-terminals, at least another terminal connector of the two or more terminal connectors is configured to electrically connect to a power device.
3. The base plate of claim 1, wherein, in the at least one multi-terminal of the at least three multi-terminals, at least another terminal connector of the two or more terminal connectors is configured to mechanically connect to a power device.
4. The base plate of claim 1, wherein, in the at least one multi-terminal of the at least three multi-terminals, at least another terminal connector of the two or more terminal connectors is configured to connect to a power source.
5. The base plate of claim 1, wherein, in the at least one multi-terminal of the at least three multi-terminals, at least another terminal connector of the two or more terminal connectors is configured to connect to a load group.
6. The base plate of claim 1, wherein one of the two or more terminal connectors in one of the at least three multi-terminals is configured to connect to one of the two or more terminal connectors of a different one of the at least three multi-terminals via a jumper.
7. The base plate of claim 1, wherein the at least one multi-terminal of the at least three multi-terminals comprises three terminal connectors.
8. The base plate of claim 1, wherein the frame is configured to mechanically connect to a mounting.
9. The base plate of claim 1, wherein the frame is configured to mechanically connect to an electrical distribution panel.
10. The base plate of claim 1, wherein the curved track is J-shaped.
11. The base plate of claim 1, wherein the curved track is C-shaped.
12. The base plate of claim 1, wherein the curved track further comprises: a funnel region; a curved central track region connected to the funnel region; and a curved end track region connected to the curved central track region.
13. The base plate of claim 12, wherein a radius of the curved end track region is less than a radius of the curved central track region.
14. The base plate of claim 13, wherein the radius of the curved end track region is at least 10% less than the radius of the curved central track region.
15. The base plate of claim 13, wherein the radius of the curved end track region is in a range of about 5 mm to about 45 mm.
16. The base plate of claim 13, wherein the radius of the curved central track region is in a range of about 20 mm to about 50 mm.
17. The base plate of claim 12, wherein the funnel region is defined by at least one curved edge.
18. The base plate of claim 12, wherein the funnel region is defined by two edges.
19. The base plate of claim 18, wherein the two edges are non-parallel edges.

20. The base plate of claim 18, wherein a distance between the two edges increases as a distance from the curved central track region increases.

---