

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12413736
Kind Code	B2
Date of Patent	September 09, 2025
Inventor(s)	Yu; Yue et al.

History-based rice parameter derivations for video coding

Abstract

In some embodiments, a video decoder decodes a video from a bitstream of the video using a history-based Rice parameter derivation. The video decoder accesses a binary string representing a partition of the video and processes each coding tree unit (CTU) in the partition to generate decoded coefficient values in the CTU. The process includes updating a history counter for a color component for calculating Rice parameters and prior to calculating a next Rice parameter, updating a replacement variable based on the updated history counter. The process further includes calculating the Rice parameters for transform units (TUs) in the CTU based on the value of the replacement variable and decoding the binary string corresponding to the TUs in the CTU into coefficient values of the TUs based on the calculated Rice parameters.

Inventors:	Yu; Yue (Palo Alto, CA), Yu; Haoping (Palo Alto, CA)
Applicant:	GUANGDONG OPPO MOBILE TELECOMMUNICATIONS CORP., LTD. (Dongguan, CN)
Family ID:	85241054
Assignee:	GUANGDONG OPPO MOBILE TELECOMMUNICATIONS CORP., LTD. (Dongguan, CN)
Appl. No.:	18/682366
Filed (or PCT Filed):	August 18, 2022
PCT No.:	PCT/US2022/075157
PCT Pub. No.:	WO2023/023608
PCT Pub. Date:	February 23, 2023

Prior Publication Data

Document Identifier	Publication Date
----------------------------	-------------------------

Related U.S. Application Data

us-provisional-application US 63250969 20210930

us-provisional-application US 63234634 20210818

Publication Classification

Int. Cl.: H04N19/134 (20140101); H04N19/119 (20140101); H04N19/18 (20140101);
H04N19/186 (20140101); H04N19/96 (20140101)

U.S. Cl.:

CPC H04N19/134 (20141101); H04N19/119 (20141101); H04N19/18 (20141101);
H04N19/186 (20141101); H04N19/96 (20141101);

Field of Classification Search

CPC: H04N (19/91); H04N (19/13); H04N (19/176); H04N (19/96); H04N (19/70); H04N
(19/119); H04N (19/186); H04N (19/18); H04N (19/134); G01N (21/88)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2013/0202029	12/2012	Lou	N/A	N/A
2017/0064336	12/2016	Zhang	N/A	N/A
2019/0104312	12/2018	Lim	N/A	N/A
2021/0306638	12/2020	Kang	N/A	H04N 19/513
2021/0392357	12/2020	Xu	N/A	H04N 19/70
2022/0182667	12/2021	Li	N/A	H04N 19/11
2024/0137499	12/2023	Solovyev	N/A	H04N 19/52

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
107925764	12/2017	CN	N/A
3709657	12/2019	EP	N/A
2021127723	12/2020	WO	N/A

OTHER PUBLICATIONS

Nguyen et al. "Transform Coding Techniques in HEVC"; Published in: IEEE Journal of Selected Topics in Signal Processing (vol. 7, Issue: 6, Dec. 2013); Date of Publication: Aug. 15, 2013; DOI: 10.1109/JSTSP.2013.2278071, entire document. 12 pages. cited by applicant

Peng et al. "Overview of Screen Content Video Coding: Technologies, Standards, and Beyond"; Published in: IEEE Journal on Emerging and Selected Topics in Circuits and Systems (vol. 6, Issue: 4, Dec. 2016); Date of Publication: Dec. 5, 2016; DOI: 10.1109/JETCAS.2016.2608971, entire document. 16 pages. cited by applicant

International Search Report in the international application No. PCT/US2022/075157, mailed on

Feb. 17, 2023. 4 pages. cited by applicant

Written Opinion of the International Search Authority in the international application No.

PCT/US2022/075157, mailed on Feb. 17, 2023. 9 pages. cited by applicant

Rusanovskyy (Qualcomm) D et al: "CE-related: On history-enhanced method of Rice parameter derivation for regular residual coding (RRC) at high bit depths", 22. JVET Meeting; 20210420 -20210428; Teleconference; (The Joint Video Exploration Team of ISO/IEC JTC1/SC29/WG11 and ITU-T SG.16), No. JVET-V0106; m56518, Apr. 19, 2021 (Apr. 19, 2021), XP030294256, section 3. cited by applicant

Rusanovskyy (Qualcomm) D et al: "CE-1.1, CE-1.2 and CE-1.4: On the Rice parameter derivation for high bit-depth coding", 22. Jvet Meeting; 20210420 -20210428; Teleconference; (The Joint Video Exploration Team of ISO/IEC JTC1/SC29/WG11 and ITU-T SG.16), No. JVET-V0052 ; m56433, Apr. 15, 2021 (Apr. 15, 2021), XP030294047, section 4. cited by applicant

Supplementary European Search Report in the European application No. 22859393.5, mailed on May 19, 2025, 11 pages. cited by applicant

First Office Action of the Chinese application No. 202411349590.9, issued on mailed on May 22, 2025, 17 pages with English translation. cited by applicant

Second Office Action of the Chinese application No. 202411349590.9, issued on Jul. 23, 2025, 18 pages with English translation. cited by applicant

Primary Examiner: Mikeska; Neil R

Attorney, Agent or Firm: BAYES PLLC

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a national stage application of International Patent Application No. PCT/US2022/075157, filed on Aug. 18, 2022, which claims priority to U.S. Provisional Application No. 63/234,634, entitled "History-Based Rice Parameter Derivations for Video Coding," filed on Aug. 18, 2021, and U.S. Provisional Application No. 63/250,969, entitled "History-Based Rice Parameter Derivations for Video Coding," filed on Sep. 30, 2021, which are hereby incorporated in their entirety by this reference.

BACKGROUND

(1) The ubiquitous camera-enabled devices, such as smartphones, tablets, and computers, have made it easier than ever to capture videos or images. However, the amount of data for even a short video can be substantially large. Video coding technology (including video encoding and decoding) allows video data to be compressed into smaller sizes thereby allowing various videos to be stored and transmitted. Video coding has been used in a wide range of applications, such as digital TV broadcast, video transmission over the internet and mobile networks, real-time applications (e.g., video chat, video conferencing), DVD and Blu-ray discs, and so on. To reduce the storage space for storing a video and/or the network bandwidth consumption for transmitting a video, it is desired to improve the efficiency of the video coding scheme.

SUMMARY

(2) This disclosure relates generally to computer-implemented methods and systems for video processing. Specifically, the present disclosure involves history-based Rice parameter derivations for video coding. In one example, a method for decoding a video includes: accessing a binary string representing a partition of the video, the partition comprising a plurality of coding tree units (CTUs); decoding each CTU of the plurality of CTUs in the partition, decoding the CTU comprising: updating a history counter StatCoeff for a color component for calculating Rice

parameters; prior to calculating a next Rice parameter, updating a replacement variable HistValue based on the updated history counter; calculating the Rice parameters for transform units (TUs) in the CTU based on the updated replacement variable HistValue; decoding the binary string corresponding to the TUs in the CTU into coefficient values of the TUs based on the calculated Rice parameters; and determining pixel values for the TUs in the CTU from the coefficient values; and outputting a decoded partition of the video comprising the decoded plurality of CTUs in the partition.

(3) In another example, a system includes a processing device; and a non-transitory computer-readable medium communicatively coupled to the processing device, wherein the processing device is configured to execute program code stored in the non-transitory computer-readable medium and thereby perform operations comprising: accessing a binary string representing a partition of a video, the partition comprising a plurality of coding tree units (CTUs); decoding each CTU of the plurality of CTUs in the partition, decoding the CTU comprising: updating a history counter StatCoeff for a color component for calculating Rice parameters: prior to calculating a next Rice parameter, updating a replacement variable HistValue based on the updated history counter; calculating the Rice parameters for transform units (TUs) in the CTU based on the updated replacement variable HistValue; decoding the binary string corresponding to the TUs in the CTU into coefficient values of the TUs based on the calculated Rice parameters; and determining pixel values for the TUs in the CTU from the coefficient values; and outputting a decoded partition of the video comprising the decoded plurality of CTUs in the partition.

(4) In another example, a method for encoding a video includes accessing a partition of the video, the partition comprising a plurality of coding tree units (CTUs); processing the partition of the video to generate a binary representation of the partition, the processing comprising: encoding each CTU of the plurality of CTUs in the partition, encoding the CTU comprising: updating a history counter StatCoeff for a color component for calculating Rice parameters; prior to calculating a next Rice parameter, updating a replacement variable HistValue based on the updated history counter; calculating the Rice parameters for transform units (TUs) in the CTU based on the updated replacement variable HistValue; and encoding coefficient values of the TUs into a binary representation corresponding to the TUs in the CTU based on the calculated Rice parameters; and encoding the binary representation of the partition into a bitstream of the video.

(5) These illustrative embodiments are mentioned not to limit or define the disclosure, but to provide examples to aid understanding thereof. Additional embodiments are discussed in the Detailed Description, and further description is provided there.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) Features, embodiments, and advantages of the present disclosure are better understood when the following Detailed Description is read with reference to the accompanying drawings.

(2) FIG. 1 is a block diagram showing an example of a video encoder configured to implement embodiments presented herein.

(3) FIG. 2 is a block diagram showing an example of a video decoder configured to implement embodiments presented herein.

(4) FIG. 3 depicts an example of a coding tree unit division of a picture in a video, according to some embodiments of the present disclosure.

(5) FIG. 4 depicts an example of a coding unit division of a coding tree unit, according to some embodiments of the present disclosure.

(6) FIG. 5 depicts an example of a coding block with a pre-determined order for processing the elements of the coding block.

- (7) FIG. 6 depicts an example of a template pattern for calculating a local sum variable for a coefficient located near a transform unit boundary.
- (8) FIG. 7 depicts an example of a process for encoding a partition for a video according to some embodiments of the present disclosure.
- (9) FIG. 8 depicts an example of a process for decoding a partition of a video according to some embodiments of the present disclosure.
- (10) FIG. 9 depicts an example of a computing system that can be used to implement some embodiments of the present disclosure.

DETAILED DESCRIPTION

- (11) Various embodiments provide history-based Rice parameter derivations for video coding. As discussed above, more and more video data are being generated, stored, and transmitted. It is beneficial to increase the efficiency of the video coding technology thereby using less data to represent a video without compromising the visual quality of the decoded video. One way to improve the coding efficiency is through entropy coding to compress processed video samples into a binary bitstream using as few bits as possible.
- (12) In entropy coding, transform coefficient data are binarized to binary bins and coding algorithms such as context-adaptive binary arithmetic coding (CABAC) can further compress bins into bits. The binarization requires the calculation of a binarization parameter, such as the Rice parameter used in a combination of truncated Rice (TR) and limited k-th order Exp-Golomb (EGk) binarization process as specified in the Versatile Video Coding (VVC) specification. To improve the coding efficiency, a method of history-based Rice parameter derivation is used. In this method, the Rice parameter for a transform unit (TU) in a current coding tree unit (CTU) of a partition (e.g., a picture, a slice, or a tile) is derived based on a history counter (denoted as StatCoeff) calculated according to coefficients in previous TUs in the current CTU and previous CTU(s) in the partition. The history counter is then used to derive a replacement variable (denoted as HistValue) to be used to derive the Rice parameter. The history counter may be updated when processing a TU. In the exiting video coding standard, the replacement variable HistValue remains unchanged for the TU even if the history counter has been updated. In other words, the replacement variable HistValue is only updated according to the updated history counter StatCoeff until the next TU. As a result, the Rice parameters calculated for the remaining positions within the current TU using the un-updated replacement variable HistValue and the updated history counter StatCoeff may lead to a reduced coding efficiency.
- (13) Various embodiments described herein address these problems by updating the replacement variable HistValue whenever the history counter StatCoeff is updated so that the updates of the replacement variable HistValue and the history counter StatCoeff are synchronized thereby improving the coding efficiency. The following non-limiting examples are provided to introduce some embodiments.
- (14) In one embodiment, the replacement variable HistValue is updated once the history counter StatCoeff is updated. In this way, the remaining positions within the current TU are coded using the updated history counter StatCoeff and the corresponding updated replacement variable HistValue until the replacement variable HistValue and the history counter StatCoeff are updated again. In a further embodiment, in addition to synchronously updating the history counter StatCoeff and replacement variable HistValue, the history counter StatCoeff is updated independently from previous history counter values. By removing the dependency among history counters, video coding can be implemented more efficiently, such as through parallel processing. In another embodiment, because updating the replacement variable HistValue is performed along with the update of the history counter StatCoeff, the steps for initializing the replacement variable HistValue at the beginning of processing each TU can be eliminated to save computational power.
- (15) Using the Rice parameter determined as discussed above, the video encoder can binarize the prediction residual data (e.g., the quantized transform coefficients of residuals) into binary bins and

use entropy coding algorithms to further compress bins into bits to be included in video bitstreams. At the decoder side, the decoder can decode the bitstream back to binary bins and determine the Rice parameter using any method or any combination of methods described above and subsequently determine the coefficients from the binary bins. The coefficients can be further de-quantized and inverse transformed to reconstruct the video blocks for display.

(16) As described herein, some embodiments provide improvements in video coding efficiency and computational efficiency by synchronizing the updates of the replacement variable HistValue and the history counter StatCoeff and removing the dependencies between history counters for different TU. By doing so, the replacement variable HistValue corresponding to the updated history counter StatCoeff can be used to derive the Rice parameter for a TU and parallel processing can be implemented to speed up the processing. The techniques can be an effective coding tool in future video coding standards.

(17) Referring now to the drawings, FIG. 1 is a block diagram showing an example of a video encoder **100** configured to implement embodiments presented herein. In the example shown in FIG. 1, the video encoder **100** includes a partition module **112**, a transform module **114**, a quantization module **115**, an inverse quantization module **118**, an inverse transform module **119**, an in-loop filter module **120**, an intra prediction module **126**, an inter prediction module **124**, a motion estimation module **122**, a decoded picture buffer **130**, and an entropy coding module **116**.

(18) The input to the video encoder **100** is an input video **102** containing a sequence of pictures (also referred to as frames or images). In a block-based video encoder, for each of the pictures, the video encoder **100** employs a partition module **112** to partition the picture into blocks **104**, and each block contains multiple pixels. The blocks may be macroblocks, coding tree units, coding units, prediction units, and/or prediction blocks. One picture may include blocks of different sizes and the block partitions of different pictures of the video may also differ. Each block may be encoded using different predictions, such as intra prediction or inter prediction or intra and inter hybrid prediction.

(19) Usually, the first picture of a video signal is an intra-predicted picture, which is encoded using only intra prediction. In the intra prediction mode, a block of a picture is predicted using only data from the same picture. A picture that is intra-predicted can be decoded without information from other pictures. To perform the intra-prediction, the video encoder **100** shown in FIG. 1 can employ the intra prediction module **126**. The intra prediction module **126** is configured to use reconstructed samples in reconstructed blocks **136** of neighboring blocks of the same picture to generate an intra-prediction block (the prediction block **134**). The intra prediction is performed according to an intra-prediction mode selected for the block. The video encoder **100** then calculates the difference between block **104** and the intra-prediction block **134**. This difference is referred to as residual block **106**.

(20) To further remove the redundancy from the block, the residual block **106** is transformed by the transform module **114** into a transform domain by applying a transform to the samples in the block. Examples of the transform may include, but are not limited to, a discrete cosine transform (DCT) or discrete sine transform (DST). The transformed values may be referred to as transform coefficients representing the residual block in the transform domain. In some examples, the residual block may be quantized directly without being transformed by the transform module **114**. This is referred to as a transform skip mode.

(21) The video encoder **100** can further use the quantization module **115** to quantize the transform coefficients to obtain quantized coefficients. Quantization includes dividing a sample by a quantization step size followed by subsequent rounding, whereas inverse quantization involves multiplying the quantized value by the quantization step size. Such a quantization process is referred to as scalar quantization. Quantization is used to reduce the dynamic range of video samples (transformed or non-transformed) so that fewer bits are used to represent the video samples.

(22) The quantization of coefficients/samples within a block can be done independently and this

kind of quantization method is used in some existing video compression standards, such as H.264, and HEVC. For an N-by-M block, a specific scan order may be used to convert the 2D coefficients of a block into a 1-D array for coefficient quantization and coding. Quantization of a coefficient within a block may make use of the scan order information. For example, the quantization of a given coefficient in the block may depend on the status of the previous quantized value along the scan order. In order to further improve the coding efficiency, more than one quantizer may be used. Which quantizer is used for quantizing a current coefficient depends on the information preceding the current coefficient in encoding/decoding scan order. Such a quantization approach is referred to as dependent quantization.

(23) The degree of quantization may be adjusted using the quantization step sizes. For instance, for scalar quantization, different quantization step sizes may be applied to achieve finer or coarser quantization. Smaller quantization step sizes correspond to finer quantization, whereas larger quantization step sizes correspond to coarser quantization. The quantization step size can be indicated by a quantization parameter (QP). The quantization parameters are provided in the encoded bitstream of the video such that the video decoder can apply the same quantization parameters for decoding.

(24) The quantized samples are then coded by the entropy coding module **116** to further reduce the size of the video signal. The entropy encoding module **116** is configured to apply an entropy encoding algorithm to the quantized samples. In some examples, the quantized samples are binarized into binary bins and coding algorithms further compress the binary bins into bits. Examples of the binarization methods include, but are not limited to, truncated Rice (TR) and limited k-th order Exp-Golomb (EGk) binarization. To improve the coding efficiency, a method of history-based Rice parameter derivation is used, where the Rice parameter derived for a transform unit (TU) is based on a variable obtained or updated from previous TUs. Examples of the entropy encoding algorithm include, but are not limited to, a variable length coding (VLC) scheme, a context adaptive VLC scheme (CAVLC), an arithmetic coding scheme, a binarization, a context-adaptive binary arithmetic coding (CABAC), syntax-based context-adaptive binary arithmetic coding (SBAC), probability interval partitioning entropy (PIPE) coding, or other entropy encoding techniques. The entropy-coded data is added to the bitstream of the output encoded video **132**.

(25) As discussed above, reconstructed blocks **136** from neighboring blocks are used in the intra-prediction of blocks of a picture. Generating the reconstructed block **136** of a block involves calculating the reconstructed residuals of this block. The reconstructed residual can be determined by applying inverse quantization and inverse transform to the quantized residual of the block. The inverse quantization module **118** is configured to apply the inverse quantization to the quantized samples to obtain de-quantized coefficients. The inverse quantization module **118** applies the inverse of the quantization scheme applied by the quantization module **115** by using the same quantization step size as the quantization module **115**. The inverse transform module **119** is configured to apply the inverse transform of the transform applied by the transform module **114** to the de-quantized samples, such as inverse DCT or inverse DST. The output of the inverse transform module **119** is the reconstructed residuals for the block in the pixel domain. The reconstructed residuals can be added to the prediction block **134** of the block to obtain a reconstructed block **136** in the pixel domain. For blocks where the transform is skipped, the inverse transform module **119** is not applied to those blocks. The de-quantized samples are the reconstructed residuals for the blocks.

(26) Blocks in subsequent pictures following the first intra-predicted picture can be coded using either inter prediction or intra prediction. In inter-prediction, the prediction of a block in a picture is from one or more previously encoded video pictures. To perform inter prediction, the video encoder **100** uses an inter prediction module **124**. The inter prediction module **124** is configured to perform motion compensation for a block based on the motion estimation provided by the motion estimation module **122**.

(27) The motion estimation module **122** compares a current block **104** of the current picture with decoded reference pictures **108** for motion estimation. The decoded reference pictures **108** are stored in a decoded picture buffer **130**. The motion estimation module **122** selects a reference block from the decoded reference pictures **108** that best matches the current block. The motion estimation module **122** further identifies an offset between the position (e.g., x, y coordinates) of the reference block and the position of the current block. This offset is referred to as the motion vector (MV) and is provided to the inter prediction module **124**. In some cases, multiple reference blocks are identified for the block in multiple decoded reference pictures **108**. Therefore, multiple motion vectors are generated and provided to the inter prediction module **124**.

(28) The inter prediction module **124** uses the motion vector(s) along with other inter-prediction parameters to perform motion compensation to generate a prediction of the current block, i.e., the inter prediction block **134**. For example, based on the motion vector(s), the inter prediction module **124** can locate the prediction block(s) pointed to by the motion vector(s) in the corresponding reference picture(s). If there are more than one prediction block, these prediction blocks are combined with some weights to generate a prediction block **134** for the current block.

(29) For inter-predicted blocks, the video encoder **100** can subtract the inter-prediction block **134** from the block **104** to generate the residual block **106**. The residual block **106** can be transformed, quantized, and entropy coded in the same way as the residuals of an intra-predicted block discussed above. Likewise, the reconstructed block **136** of an inter-predicted block can be obtained through inverse quantizing, inverse transforming the residual, and subsequently combining with the corresponding prediction block **134**.

(30) To obtain the decoded picture **108** used for motion estimation, the reconstructed block **136** is processed by an in-loop filter module **120**. The in-loop filter module **120** is configured to smooth out pixel transitions thereby improving the video quality. The in-loop filter module **120** may be configured to implement one or more in-loop filters, such as a de-blocking filter, or a sample-adaptive offset (SAO) filter, or an adaptive loop filter (ALF), etc.

(31) FIG. 2 depicts an example of a video decoder **200** configured to implement embodiments presented herein. The video decoder **200** processes an encoded video **202** in a bitstream and generates decoded pictures **208**. In the example shown in FIG. 2, the video decoder **200** includes an entropy decoding module **216**, an inverse quantization module **218**, an inverse transform module **219**, an in-loop filter module **220**, an intra prediction module **226**, an inter prediction module **224**, and a decoded picture buffer **230**.

(32) The entropy decoding module **216** is configured to perform entropy decoding of the encoded video **202**. The entropy decoding module **216** decodes the quantized coefficients, coding parameters including intra prediction parameters and inter prediction parameters, and other information. In some examples, the entropy decoding module **216** decodes the bitstream of the encoded video **202** to binary representations and then converts the binary representations to the quantization levels for the coefficients. The entropy-decoded coefficients are then inverse quantized by the inverse quantization module **218** and subsequently inverse transformed by the inverse transform module **219** to the pixel domain. The inverse quantization module **218** and the inverse transform module **219** function similarly to the inverse quantization module **118** and the inverse transform module **119**, respectively, as described above with respect to FIG. 1. The inverse-transformed residual block can be added to the corresponding prediction block **234** to generate a reconstructed block **236**. For blocks where the transform is skipped, the inverse transform module **219** is not applied to those blocks. The de-quantized samples generated by the inverse quantization module **118** are used to generate the reconstructed block **236**.

(33) The prediction block **234** of a particular block is generated based on the prediction mode of the block. If the coding parameters of the block indicate that the block is intra predicted, the reconstructed block **236** of a reference block in the same picture can be fed into the intra prediction module **226** to generate the prediction block **234** for the block. If the coding parameters of the

block indicate that the block is inter-predicted, the prediction block **234** is generated by the inter prediction module **224**. The intra prediction module **226** and the inter prediction module **224** function similarly to the intra prediction module **126** and the inter prediction module **124** of FIG. 1, respectively.

(34) As discussed above with respect to FIG. 1, the inter prediction involves one or more reference pictures. The video decoder **200** generates the decoded pictures **208** for the reference pictures by applying the in-loop filter module **220** to the reconstructed blocks of the reference pictures. The decoded pictures **208** are stored in the decoded picture buffer **230** for use by the inter prediction module **224** and also for output.

(35) Referring now to FIG. 3, FIG. 3 depicts an example of a coding tree unit division of a picture in a video, according to some embodiments of the present disclosure. As discussed above with respect to FIGS. 1 and 2, to encode a picture of a video, the picture is divided into blocks, such as the CTUs (Coding Tree Units) **302** in VVC, as shown in FIG. 3. For example, the CTUs **302** can be blocks of 128×128 pixels. The CTUs are processed according to an order, such as the order shown in FIG. 3. In some examples, each CTU **302** in a picture can be partitioned into one or more CUs (Coding Units) **402** as shown in FIG. 4, which can be further partitioned into prediction units or transform units (TUs) for prediction and transformation. Depending on the coding schemes, a CTU **302** may be partitioned into CUs **402** differently. For example, in VVC, the CUs **402** can be rectangular or square and can be coded without further partitioning into prediction units or transform units. Each CU **402** can be as large as its root CTU **302** or be subdivisions of a root CTU **302** as small as 4×4 blocks. As shown in FIG. 4, a division of a CTU **302** into CUs **402** in VVC can be quadtree splitting or binary tree splitting or ternary tree splitting. In FIG. 4, solid lines indicate quadtree splitting and dashed lines indicate binary or ternary tree splitting.

(36) As discussed above with respect to FIGS. 1 and 2, quantization is used to reduce the dynamic range of elements of blocks in the video signal so that fewer bits are used to represent the video signal. In some examples, before quantization, an element at a specific position of the block is referred to as a coefficient. After quantization, the quantized value of the coefficient is referred to as a quantization level or a level. Quantization typically consists of division by a quantization step size and subsequent rounding while inverse quantization consists of multiplication by the quantization step size. Such a quantization process is also referred to as scalar quantization. The quantization of the coefficients within a block can be performed independently and this kind of independent quantization method is used in some existing video compression standards, such as H.264, HEVC, etc. In other examples, dependent quantization is employed, such as in VVC.

(37) For an N-by-M block, a specific scanning order may be used to convert 2-D coefficients of a block into a 1-D array for coefficient quantization and coding, and the same scanning order is used for both encoding and decoding. FIG. 5 shows an example of a coding block (such as a transform unit (TU)) with a pre-determined scanning order for processing the coefficients of the coding block. In this example, the coding block **500** has a size of 8×8 and the processing starts at the lower right corner at position L.sub.0 and ends at the upper left corner L.sub.63. If block **500** is a transformed block, the pre-determined order shown in FIG. 5 starts from the highest frequency to the lowest frequency. In some examples, the processing of the block, such as quantization and binarization, starts from the first non-zero element of the block according to the pre-determined scanning order. For instance, if the coefficients at locations L.sub.0-L.sub.17 are all zero and the coefficient at L.sub.18 is non-zero, then the processing starts at the coefficient at L.sub.18 and is performed for each coefficient after L.sub.18 in the scanning order.

(38) Residual Coding

(39) Residual coding is used to convert the quantization levels into a bit stream in video coding. After quantization, there are N×M quantization levels for an N×M transform unit (TU) coding block. These N×M levels may be zero or non-zero values. The non-zero levels will further be binarized to binary bins if the levels are not binary. Context-adaptive binary arithmetic coding

(CABAC) can further compress bins into bits. Furthermore, there are two kinds of context modeling-based coding methods. In particular, one of the methods updates the context model adaptively according to the neighboring coded information. Such a method is called context coded method, and bins coded in this way are called context coded bins. In contrast, the other method assumes the probability of 1 or 0 is always 50% and therefore always uses a fixed context modeling without adaptation. This kind of method is called as bypass method and bins coded by this method are called bypass bins.

(40) For a regular residual coding (RRC) block in VVC, the position of the last non-zero level is defined as the position of last non-zero level along the coding scanning order. The representation of the 2D coordinates (`last_sig_coeff_x` and `last_sig_coeff_y`) of the last non-zero level includes a total of 4 prefix and suffix syntax elements, which are `last_sig_coeff_x_prefix`, `last_sig_coeff_y_prefix`, `last_sig_coeff_x_suffix`, `last_sig_coeff_y_suffix`. The syntax elements `last_sig_coeff_x_prefix` and `last_sig_coeff_y_prefix` are first coded with context coded method. If `last_sig_coeff_x_suffix` and `last_sig_coeff_y_suffix` are presented, they are coded with the bypass method. A RRC block may consist of several pre-defined sub-blocks. The syntax element `sb_coded_flag` is used to indicate if the current sub-block has all the levels equal to zero or not. If `sb_coded_flag` is equal to 1, there is at least one non-zero coefficient in the current sub-block. If `sb_coded_flag` is equal to 0, all coefficients in the current sub-block will be zeros. However, the `sb_coded_flag` for the last non-zero sub-block which has the last non-zero level is derived as 1 from `last_sig_coeff_x` and `last_sig_coeff_y` according to the coding scanning order without coding into bitstream. Moreover, the `sb_coded_flag` for the top-left sub-block which contains the DC position is also derived as 1 without coding into the bitstream. The syntax elements of `sb_coded_flag` in the bitstream are coded through the context coded method. RRC will code sub-block by sub-block starting from the last non-zero sub-block with a reverse coding scanning order as discussed above with respect to FIG. 5.

(41) In order to guarantee the worst-case throughput, a pre-defined value `remBinsPass1` is used to limit the maximum number of context coded bins. Within a sub-block, RRC will code the level of each position with a reverse coding scan order. If `remBinsPass1` is greater than 4, when coding the current level, a flag, named as `sig_coeff_flag`, is first coded into the bitstream to indicate if the level is zero or non-zero. If the level is non-zero, the `abs_level_gtx_flag[n][0]` where n is the index along the scanning order of the current position within a sub-block to indicate if the absolute level is 1 or greater than 1. If the absolute level is greater than 1, the `par_level_flag` will be coded to indicate if the level is an odd or even number in VVC and then `abs_level_gtx_flag[n][1]` will be present. The flags of `par_level_flag` and `abs_level_gtx_flag[n][1]` are also used together to indicate the level is 2, or 3 or greater than 3. After coding each of the above syntax elements as a context-coded bin, the value of `remBinsPass1` will be decreased by one.

(42) If the absolute level is greater than 3 or the value of `remBinsPass1` is not greater than 4, two more syntax elements, `abs_remainder` and `dec_abs_level` may be coded as bypass-coded bins for the remaining level after coding the aforementioned bins by the context coded method. In addition, the sign of each level within a block will also be coded to represent the quantization level, and they are coded as bypass-coded bins.

(43) Another residual coding method uses `abs_level_gtxX_flag` and the remaining level to allow conditionally parsing of the syntax elements for level coding of a residual block, and the corresponding binarization of the absolute value of level is shown in Table 1. Here `abs_level_gtxX_flag` describes if the absolute value of the level is greater than X where X is an integer number, e.g., 0, 1, 2, or N . If `abs_level_gtxY_flag` is 0 where Y is an integer between 0 and $N-1$, `abs_level_gtx(Y+1)` flag will not be present. If `abs_level_gtxY_flag` is 1, `abs_level_gtx(Y+1)` flag will be present. Moreover, if `abs_level_gtxN_flag` is 0, the remaining level will not be present. When `abs_level_gtxN_flag` is 1, the remaining level will be present and it represents the value after removing $(N+1)$ from the level. Typically, `abs_level_gtxX_flag` is coded with context coded

] else locSumAbs += HistValue } else locSumAbs += HistValue

(59) Before coding each TU, the history value HistValue calculated according to Eqn. (2) is used to derive the Rice parameter for coding the first abs_remainder or dec_abs_level syntax element for each TU if possible.

(60) The history counter StatCoeff is updated once per TU from the first, non-zero, Golomb-Rice coded transform coefficient (abs_remainder[cIdx] or dec_abs_level[cIdx]) through a process of an exponential moving average. When the first, non-zero, Golomb-Rice coded transform coefficient in the TU is coded as abs_remainder, the history counter StatCoeff for color component cIdx is updated as the following:

$$(61) \text{ StatCoeff}[cIdx] = (\text{StatCoeff}[cIdx] + \text{Floor}(\text{Log2}(\text{abs_remainder}[cIdx])) + 2) \gg 1 \quad (3)$$

When the first, non-zero, Golomb-Rice coded transform coefficient in the TU is coded as dec_abs_level, the history counter StatCoeff for color component cIdx is updated as the following:

$$(62) \text{ StatCoeff}[cIdx] = (\text{StatCoeff}[cIdx] + \text{Floor}(\text{Log2}(\text{dec_abs_level}[cIdx]))) \gg 1 \quad (4)$$

The updated StatCoeff can be used to calculate the replacement variable HistValue for the next TU according to Eqn. (2) prior to decoding the next TU.

(63) While according to the above, the history counter StatCoeff is updated when the first, non-zero, Golomb-Rice coded transform coefficient in the current TU is coded as abs_remainder or dec_abs_level, the replacement variable HistValue is only updated according to the updated history counter StatCoeff until the next TU. As a result, the HistValue used to calculate the Rice parameters might not be the proper value to find the best Rice parameters for the remaining positions within current TU. In this disclosure, embodiments are described to synchronize the updates of the HistValue and the history counter StatCoeff so that the replacement variable HistValue corresponding to the updated history counter StatCoeff is used in calculating the Rice parameters.

(64) In one embodiment, when the first, non-zero, Golomb-Rice coded transform coefficient in a TU for color component cIdx is coded as abs_remainder, the history counter for color component cIdx is updated according to Eqn. (3). When the first, non-zero, Golomb-Rice coded transform coefficient in a TU for color component cIdx is coded as dec_abs_level, the history counter for color component cIdx is updated according to Eqn. (4). Once the history counter StatCoeff[cIdx] is updated, the replacement variable HistValue will be updated according to Eqn. (5) and the updated replacement variable HistValue will be used in the derivation of Rice parameter for the remaining abs_remainder and dec_abs_level syntax elements in the current TU for color component cIdx till the new StatCoeff[cIdx] and HistValue are updated again.

$$(65) \text{ HistValue} = 1 \ll \text{StatCoeff}[cIdx] \quad (5)$$

(66) Possible changes to VVC specification are specified as follows.

(67) Residual Coding Syntax

(68) Change clause 7.3.11.11 (Residual coding syntax) as follows (additions are underlined):

(69) TABLE-US-00005 Descriptor residual_coding(x0, y0, log2TbWidth, log2TbHeight, cIdx) {
... } for(n = firstPosMode0; n > firstPosMode1; n--) { xC = (xS <<
log2SbW) + DiagScanOrder[log2SbW][log2SbH][n][0] yC = (yS << log2SbH) +
DiagScanOrder[log2SbW][log2SbH][n][1] if(abs_level_gtx_flag[n][1]) {
abs_remainder[n] ae(v) if(updateHist && abs_remainder[n] > 0) {
StatCoeff[cIdx] = (StatCoeff[cIdx] + Floor(Log2(abs_remainder[n]
)) + 2) >> 1 updateHist = 0 HistValue = 1 << StatCoeff[cIdx]
} } AbsLevel[xC][yC] = AbsLevelPass1[xC][yC] + 2 *
abs_remainder[n] } for(n = firstPosMode1; n >= 0; n--) { xC = (xS <<
log2SbW) + DiagScanOrder[log2SbW][log2SbH][n][0] yC = (yS << log2SbH) +
DiagScanOrder[log2SbW][log2SbH][n][1] if(sb_coded_flag[xS][yS]) {
dec_abs_level[n] ae(v) if(updateHist && dec_abs_level[n] > 0) {
StatCoeff[cIdx] = (StatCoeff[cIdx] + Floor(Log2(dec_abs_level[n]))) >> 1

```

updateHist = 0 HistValue = 1 << StatCoeff[ cIdx ] }
if( AbsLevel[ xC ][ yC ] > 0 ) { if( lastSigScanPosSb == -1 )
lastSigScanPosSb = n firstSigScanPosSb = n } if(
sh_dep_quant_used_flag ) QState = QStateTransTable[ QState ][ AbsLevel[ xC ][ yC ] &
1 ] } .....

```

(70) In another embodiment, in addition to synchronously updating the history counter StatCoeff and replacement variable HistValue, the history counter StatCoeff is updated independently from previous history counter values. By removing the dependency among history counters, video coding can be implemented more efficiently, such as through parallel processing.

(71) In this embodiment, when the first non-zero Golomb-Rice coded transform coefficient in a TU is coded as abs_remainder, the history counter for color component cIdx is updated as the following:

(72) $StatCoeff[cIdx] = \text{Floor}(\text{Log2}(\text{abs_remainder}[cIdx])) + 1$ (6)

When the first non-zero Golomb-Rice coded transform coefficient in TU is coded as dec_abs_level, the history counter for color component cIdx is updated as the following:

(73) $StatCoeff[cIdx] = \text{Floor}(\text{Log2}(\text{dec_abs_level}[cIdx]))$ (7)

Once the history counter StatCoeff[cIdx] is updated, the HistValue will be updated according to Eqn. (5) and the updated HistValue will be used in the derivation of Rice parameter for the remaining abs_remainder and dec_abs_level syntax elements in the current TU for color component cIdx till the new StatCoeff[cIdx] and HistValue are updated again.

(74) Possible changes to VVC specification are specified as follows.

(75) Residual Coding Syntax

(76) Change clause 7.3.11.11 (Residual coding syntax) as follows (additions are underlined and content with strikethrough will be removed):

(77) TABLE-US-00006 Descriptor residual_coding(x0, y0, log2TbWidth, log2TbHeight, cIdx) {
... } for(n = firstPosMode0; n > firstPosMode1; n--) { xC = (xS <<
log2SbW) + DiagScanOrder[log2SbW][log2SbH][n][0] yC = (yS << log2SbH) +
DiagScanOrder[log2SbW][log2SbH][n][1] if(abs_level_gtx_flag[n][1]) {
abs_remainder[n] ae(v) if(updateHist && abs_remainder[n] > 0) {
StatCoeff[cIdx] =  Floor(Log2(abs_remainder[n]
)) + 1  updateHist = 0 HistValue = 1 << StatCoeff[cIdx]
AbsLevelPass1[xC][yC] + 2 * abs_remainder[n] } } AbsLevel[xC][yC] =
AbsLevelPass1[xC][yC] + 2 * abs_remainder[n] } for(n = firstPosMode1; n >= 0; n--) {
xC = (xS << log2SbW) + DiagScanOrder[log2SbW][log2SbH][n][0] yC
= (yS << log2SbH) + DiagScanOrder[log2SbW][log2SbH][n][1] if(sb_coded_flag[
xS][yS]) { dec_abs_level[n] ae(v) if(updateHist && dec_abs_level[n] >
0) { StatCoeff[cIdx] =  Floor(Log2(
dec_abs_level[n]))  updateHist = 0 HistValue = 1
<< StatCoeff[cIdx] } } if(AbsLevel[xC][yC] > 0) { if(
lastSigScanPosSb == -1) lastSigScanPosSb = n firstSigScanPosSb = n
} if(sh_dep_quant_used_flag) QState = QStateTransTable[QState][
AbsLevel[xC][yC] & 1] }

(78) As can be seen from the above, the StatCoeff is determined based on the abs_remainder or the dec_abs_level and is independent of the previous StatCoeff values. As a result, the StatCoeff values for different TUs are independent of each other.

(79) In another embodiment, because updating the replacement variable HistValue is performed along with the update of the history counter StatCoeff, the steps for initializing the replacement variable HistValue at the beginning of processing each TU can be eliminated to save computational power.

(80) In this embodiment, if the CTU is the first CTU in a slice or tile, the replacement variable HistValue is initialed with initial StatCoeff[cIdx] as follows:

(81) $\text{HistValue} = \text{sps_persistent_rice_adaptation_enabled_flag} ? 1 \ll \text{StatCoeff}[\text{cIdx}] : 0$ (8)

This initial HistValue is used for coding till HistValue is updated according to the following rules.

(82) When the first, non-zero, Golomb-Rice coded transform coefficient in a TU is coded as abs_remainder, the history counter for color component cIdx is updated according to Eqn. (3) (or Eqn. (6)). When the first, non-zero, Golomb-Rice coded transform coefficient in a TU is coded as dec_abs_level, the history counter for color component cIdx is updated according to Eqn. (4) (or Eqn. (7)).

(83) Once the history counter StatCoeff[cIdx] is updated, the replacement variable HistValue will be updated according to Eqn. (5) and the updated replacement variable HistValue will be used in the derivation of Rice parameter for remaining abs_remainder and dec_abs_level syntax elements till the new StatCoeff[cIdx] and HistValue are updated again.

(84) Possible changes to the VVC specification are specified as follows.

(85) Residual Coding Syntax

(86) Change clause 7.3.11.11 (Residual coding syntax) as follows (additions are underlined):

(87) TABLE-US-00007 Descriptor residual_coding(x0, y0, log2TbWidth, log2TbHeight, cIdx) {
... lastScanPos = numSbCoeff lastSubBlock = (1 << (log2TbWidth + log2TbHeight - (log2SbW + log2SbH))) - 1  updateHist =
sps_persistent_rice_adaptation_enabled_flag ? 1 : 0 ... for(n = firstPosMode0; n >
firstPosMode1; n--) { xC = (xS << log2SbW) + DiagScanOrder[log2SbW][log2SbH][n][0] yC = (yS << log2SbH) + DiagScanOrder[log2SbW][log2SbH][n][1]
if(abs_level_gtx_flag[n][1]) { abs_remainder[n] ae(v) if(updateHist &&
abs_remainder[n] > 0) { StatCoeff[cIdx] = (StatCoeff[cIdx] +
Floor(Log2(abs_remainder[n])) + 2) >> 1 updateHist = 0
HistValue = 1 << StatCoeff[cIdx] } } AbsLevel[xC][yC] =
AbsLevelPass1[xC][yC] + 2 * abs_remainder[n] } for(n = firstPosMode1; n >= 0; n--) {
xC = (xS << log2SbW) + DiagScanOrder[log2SbW][log2SbH][n][0] yC
= (yS << log2SbH) + DiagScanOrder[log2SbW][log2SbH][n][1] if(sb_coded_flag[
xS][yS]) { dec_abs_level[n] ae(v) if(updateHist && dec_abs_level[n] > 0)
{ StatCoeff[cIdx] = (StatCoeff[cIdx] + Floor(Log2(
dec_abs_level[n]))) >> 1 updateHist = 0 HistValue = 1 << StatCoeff[cIdx]
} } if(AbsLevel[xC][yC] > 0) { if(lastSigScanPosSb
== -1) lastSigScanPosSb = n firstSigScanPosSb = n } if(
sh_dep_quant_used_flag) QState = QStateTransTable[QState][AbsLevel[xC][yC] &
1] }

(88) Because the replacement variable HistValue is updated each time the history counter StatCoeff is updated and the value of the replacement variable HistValue from the previous TU is stored in the replacement variable HistValue, there is no need to initialize the replacement variable HistValue at the beginning of processing each TU. As such, the initialization step can be removed as shown above to save the computing power of the video encoder and decoder.

(89) FIG. 7 depicts an example of a process 700 for encoding a partition for a video, according to some embodiments of the present disclosure. One or more computing devices (e.g., the computing device implementing the video encoder 100) implement operations depicted in FIG. 7 by executing suitable program code (e.g., the program code implementing the entropy coding module 116). For illustrative purposes, the process 700 is described with reference to some examples depicted in the figures. Other implementations, however, are possible.

(90) At block 702, the process 700 involves accessing a partition of a video signal. The partition can be a video frame, a slice, a tile, or any type of partition processed by a video encoder as a unit

when performing the encoding. The partition includes a set of CTUs and each CTU includes one or more CUs and each CU includes multiple TUs for encoding as shown in the example of FIG. 6.

(91) At block **704**, which includes **706-712**, the process **700** involves processing each CTU of the set of CTUs in the partition to encode the partition into bits. At block **706**, the process **700** involves updating the replacement variable HistValue and the history counter StatCoeff together. As discussed above, in some embodiments, updating the history counter StatCoeff can be performed according to Eqn. (3) and Eqn. (4) when the first, non-zero, Golomb-Rice coded transform coefficient in a TU is coded as abs_remainder and dec_abs_level, respectively. In other embodiments, updating the history counter StatCoeff can be performed according to Eqn. (6) and Eqn. (7) when the first, non-zero, Golomb-Rice coded transform coefficient in a TU is coded as abs_remainder and dec_abs_level, respectively.

(92) In either case, the replacement variable HistValue is updated whenever the history counter StatCoeff is updated. For example, if the replacement variable HistValue is updated according to Eqn. (3) (or Eqn. (6)), the history counter StatCoeff is updated according to Eqn. (5) based on the updated value of the history counter StatCoeff. Likewise, if the replacement variable HistValue is updated according to Eqn. (4) (or Eqn. (7)), the history counter StatCoeff is updated according to Eqn. (5) based on the updated value of the history counter StatCoeff. In this way, before the next Rice parameter is calculated, both the history counter StatCoeff and the replacement variable HistValue are updated.

(93) At block **708**, the Rice parameters for the TUs in the CTU are calculated as discussed above based on the updated replacement variable HistValue. At block **710**, the process **700** involves encoding the TUs in the CTU into binary representation based on the calculated Rice parameters, such as through a combination of truncated Rice (TR) and limited k-th order EGK as specified in the VVC specification. At block **712**, the process **700** involves encoding the binary representation of the CTU into the bits for inclusion in the bitstream of the video. The encoding can be performed, for example, using the context-adaptive binary arithmetic coding (CABAC) discussed above. At block **714**, the process **700** involves output the encoded video bitstream.

(94) FIG. 8 depicts an example of a process **800** for decoding a partition for a video, according to some embodiments of the present disclosure. One or more computing devices implement operations depicted in FIG. 8 by executing suitable program code. For example, a computing device implementing the video decoder **200** may implement the operations depicted in FIG. 8 by executing the program code for the entropy decoding module **216**, the inverse quantization module **218**, and the inverse transform module **219**. For illustrative purposes, the process **800** is described with reference to some examples depicted in the figures. Other implementations, however, are possible.

(95) At block **802**, the process **800** involves accessing a binary string or a binary representation that represents a partition of a video signal. The partition can be a video frame, a slice, or a tile or any type of partition processed by a video encoder as a unit when performing the encoding. The partition includes a set of CTUs. Each CTU includes one or more CUs and each CU includes multiple TUs for encoding as shown in the example of FIG. 6.

(96) At block **804**, which includes **806-812**, the process **800** involves processing the binary string for each CTU of the set of CTUs in the partition to generate decoded samples for the partition. At block **806**, the process **800** involves updating the replacement variable HistValue in conjunction with the update of the history counter StatCoeff. As discussed above, in some embodiments, updating the history counter StatCoeff can be performed according to Eqn. (3) and Eqn. (4) when the first, non-zero, Golomb-Rice coded transform coefficient in a TU is coded as abs_remainder and dec_abs_level, respectively. In other embodiments, updating the history counter StatCoeff can be performed according to Eqn. (6) and Eqn. (7) when the first, non-zero, Golomb-Rice coded transform coefficient in a TU is coded as abs_remainder and dec_abs_level, respectively.

(97) In either case, the replacement variable HistValue is updated whenever the history counter

StatCoeff is updated. For example, if the replacement variable HistValue is updated according to Eqn. (3) (or Eqn. (6)), the history counter StatCoeff is updated according to Eqn. (5) based on the updated value of the history counter StatCoeff. Likewise, if the replacement variable HistValue is updated according to Eqn. (4) (or Eqn. (7)), the history counter StatCoeff is updated according to Eqn. (5) based on the updated value of the history counter StatCoeff. In this way, before the next Rice parameter is calculated, both the history counter StatCoeff and the replacement variable HistValue are updated.

(98) At block **808**, the process **800** involves calculating the Rice parameters for the TUs in the CTU as discussed above based on the updated replacement variable HistValue. At block **810**, the process **800** involves decoding the binary strings or binary representations of TUs in the CTU into coefficient values based on the calculated Rice parameters, such as through a combination of truncated Rice (TR) and limited k-th order EGK as specified in the VVC specification. At block **812**, the process **800** involves reconstructing the pixel values for the TUs in the CTU through, for example, reverse quantization and reversion transformation as discussed above with respect to FIG. 2. At block **814**, the process **800** involves outputting the decoded partition of the video.

(99) While in the above description, TUs are described and illustrated in the figures (e.g., FIG. 6), the same techniques can be applied to transform blocks (TBs). In other words, in the embodiments presented above (including the figures), TUs can also represent TBs.

(100) Computing System Example for Implementing Dependent Quantization for Video Coding

(101) Any suitable computing system can be used for performing the operations described herein. For example, FIG. 9 depicts an example of a computing device **900** that can implement the video encoder **100** of FIG. 1 or the video decoder **200** of FIG. 2. In some embodiments, the computing device **900** can include a processor **912** that is communicatively coupled to a memory **914** and that executes computer-executable program code and/or accesses information stored in the memory **914**. The processor **912** may comprise a microprocessor, an application-specific integrated circuit (“ASIC”), a state machine, or other processing device. The processor **912** can include any of a number of processing devices, including one. Such a processor can include or may be in communication with a computer-readable medium storing instructions that, when executed by the processor **912**, cause the processor to perform the operations described herein.

(102) The memory **914** can include any suitable non-transitory computer-readable medium. The computer-readable medium can include any electronic, optical, magnetic, or other storage device capable of providing a processor with computer-readable instructions or other program code. Non-limiting examples of a computer-readable medium include a magnetic disk, memory chip, ROM, RAM, an ASIC, a configured processor, optical storage, magnetic tape or other magnetic storage, or any other medium from which a computer processor can read instructions. The instructions may include processor-specific instructions generated by a compiler and/or an interpreter from code written in any suitable computer-programming language, including, for example, C, C++, C #, Visual Basic, Java, Python, Perl, JavaScript, and ActionScript.

(103) The computing device **900** can also include a bus **916**. The bus **916** can communicatively couple one or more components of the computing device **900**. The computing device **900** can also include a number of external or internal devices such as input or output devices. For example, the computing device **900** is shown with an input/output (“I/O”) interface **918** that can receive input from one or more input devices **920** or provide output to one or more output devices **922**. The one or more input devices **920** and one or more output devices **922** can be communicatively coupled to the I/O interface **918**. The communicative coupling can be implemented via any suitable manner (e.g., a connection via a printed circuit board, connection via a cable, communication via wireless transmissions, etc.). Non-limiting examples of input devices **920** include a touch screen (e.g., one or more cameras for imaging a touch area or pressure sensors for detecting pressure changes caused by a touch), a mouse, a keyboard, or any other device that can be used to generate input events in response to physical actions by a user of a computing device. Non-limiting examples of output

devices **922** include an LCD screen, an external monitor, a speaker, or any other device that can be used to display or otherwise present outputs generated by a computing device.

(104) The computing device **900** can execute program code that configures the processor **912** to perform one or more of the operations described above with respect to FIGS. **1-8**. The program code can include the video encoder **100** or the video decoder **200**. The program code may be resident in the memory **914** or any suitable computer-readable medium and may be executed by the processor **912** or any other suitable processor.

(105) The computing device **900** can also include at least one network interface device **924**. The network interface device **924** can include any device or group of devices suitable for establishing a wired or wireless data connection to one or more data networks **928**. Non-limiting examples of the network interface device **924** include an Ethernet network adapter, a modem, and/or the like. The computing device **900** can transmit messages as electronic or optical signals via the network interface device **924**.

(106) General Considerations

(107) Numerous specific details are set forth herein to provide a thorough understanding of the claimed subject matter. However, those skilled in the art will understand that the claimed subject matter may be practiced without these specific details. In other instances, methods, apparatuses, or systems that would be known by one of ordinary skill have not been described in detail so as not to obscure claimed subject matter.

(108) Unless specifically stated otherwise, it is appreciated that throughout this specification discussions utilizing terms such as “processing,” “computing,” “calculating,” “determining,” and “identifying” or the like refer to actions or processes of a computing device, such as one or more computers or a similar electronic computing device or devices, that manipulate or transform data represented as physical electronic or magnetic quantities within memories, registers, or other information storage devices, transmission devices, or display devices of the computing platform.

(109) The system or systems discussed herein are not limited to any particular hardware architecture or configuration. A computing device can include any suitable arrangement of components that provide a result conditioned on one or more inputs. Suitable computing devices include multi-purpose microprocessor-based computer systems accessing stored software that programs or configures the computing system from a general purpose computing apparatus to a specialized computing apparatus implementing one or more embodiments of the present subject matter. Any suitable programming, scripting, or other type of language or combinations of languages may be used to implement the teachings contained herein in software to be used in programming or configuring a computing device.

(110) Embodiments of the methods disclosed herein may be performed in the operation of such computing devices. The order of the blocks presented in the examples above can be varied—for example, blocks can be re-ordered, combined, and/or broken into sub-blocks. Some blocks or processes can be performed in parallel.

(111) The use of “adapted to” or “configured to” herein is meant as open and inclusive language that does not foreclose devices adapted to or configured to perform additional tasks or steps. Additionally, the use of “based on” is meant to be open and inclusive, in that a process, step, calculation, or other action “based on” one or more recited conditions or values may, in practice, be based on additional conditions or values beyond those recited. Headings, lists, and numbering included herein are for ease of explanation only and are not meant to be limiting.

(112) While the present subject matter has been described in detail with respect to specific embodiments thereof, it will be appreciated that those skilled in the art, upon attaining an understanding of the foregoing, may readily produce alterations to, variations of, and equivalents to such embodiments. Accordingly, it should be understood that the present disclosure has been presented for purposes of example rather than limitation, and does not preclude the inclusion of

such modifications, variations, and/or additions to the present subject matter as would be readily apparent to one of ordinary skill in the art.

Claims

1. A method for decoding a video, the method comprising: accessing a binary string representing a partition of the video, the partition comprising a plurality of coding tree units (CTUs); decoding each CTU of the plurality of CTUs in the partition, decoding the CTU comprising: updating a history counter StatCoeff for a color component for calculating Rice parameters; prior to calculating a next Rice parameter, updating a replacement variable HistValue based on the updated history counter; calculating the Rice parameters for transform units (TUs) in the CTU based on the updated replacement variable HistValue; decoding the binary string corresponding to the TUs in the CTU into coefficient values of the TUs based on the calculated Rice parameters; and determining pixel values for the TUs in the CTU from the coefficient values; and outputting a decoded partition of the video comprising the decoded plurality of CTUs in the partition.
2. The method of claim 1, wherein updating the history counter StatCoeff comprises: in response to determining that a first non-zero Golomb-Rice coded transform coefficient in a TU is coded as abs_remainder, updating the history counter StatCoeff for a color component cIdx as: $\text{StatCoeff}[\text{cIdx}] = \text{Floor}(\text{Log2}(\text{abs_remainder}[\text{cIdx}])) + 1$; in response to determining that the first non-zero Golomb-Rice coded transform coefficient in the TU is coded as dec_abs_level, updating the history counter for a color component cIdx as: $\text{StatCoeff}[\text{cIdx}] = \text{Floor}(\text{Log2}(\text{dec_abs_level}[\text{cIdx}]))$, wherein Floor(x) represents the largest integer less than or equal to x, and Log 2(x) is base-2 logarithm of x.
3. The method of claim 1, wherein the partition is a frame, a slice, or a tile.
4. The method of claim 1, further comprising setting the history counter StatCoeff to an initial value based on a bit depth of samples of luma and chroma arrays of the video.
5. The method of claim 1, wherein calculating the Rice parameters for the TUs in the CTU based on the history counter comprises: calculating a local sum variable locSumAbs for a coefficient in a TU of the CTU using values of neighboring coefficients in a pre-determined neighborhood of the coefficient and the replacement variable HistValue; and deriving the Rice parameter for the TU based on the local sum variable locSumAbs.
6. The method of claim 5, wherein calculating a local sum variable locSumAbs for a coefficient in a TU of the CTU comprises: determining that a neighboring coefficient of a plurality of neighboring coefficients in the pre-determined neighborhood of the coefficient is outside the TU; and using the replacement variable HistValue as a value of the neighboring coefficient outside the TU to calculate the local sum variable locSumAbs.
7. The method of claim 1, wherein updating a replacement variable HistValue based on the history counter comprises updating the replacement variable HistValue for a color component cIdx by calculating: $\text{HistValue}[\text{cIdx}] = 1 \ll \text{StatCoeff}[\text{cIdx}]$, wherein StatCoeff denotes the history counter.
8. A system comprising: a processing device; and a non-transitory computer-readable medium communicatively coupled to the processing device, wherein the processing device is configured to execute program code stored in the non-transitory computer-readable medium and thereby perform operations comprising: accessing a binary string representing a partition of a video, the partition comprising a plurality of coding tree units (CTUs); decoding each CTU of the plurality of CTUs in the partition, decoding the CTU comprising: updating a history counter StatCoeff for a color component for calculating Rice parameters; prior to calculating a next Rice parameter, updating a replacement variable HistValue based on the updated history counter; calculating the Rice parameters for transform units (TUs) in the CTU based on the updated replacement variable

HistValue; decoding the binary string corresponding to the TUs in the CTU into coefficient values of the TUs based on the calculated Rice parameters; and determining pixel values for the TUs in the CTU from the coefficient values; and outputting a decoded partition of the video comprising the decoded plurality of CTUs in the partition.

9. The system of claim 8, wherein updating the history counter StatCoeff comprises: in response to determining that a first non-zero Golomb-Rice coded transform coefficient in a TU is coded as abs_remainder, updating the history counter StatCoeff for a color component cIdx as:

StatCoeff[cIdx] = Floor(Log2(abs_remainder[cIdx])) + 1; and in response to determining that the first non-zero Golomb-Rice coded transform coefficient in the TU is coded as dec_abs_level, updating the history counter for a color component cIdx as:

StatCoeff[cIdx] = Floor(Log2(dec_abs_level[cIdx])), wherein Floor(x) represents the largest integer less than or equal to x, and Log 2(x) is base-2 logarithm of x.

10. The system of claim 8, further comprising setting the history counter StatCoeff to an initial value based on a bit depth of samples of luma and chroma arrays of the video.

11. The system of claim 8, wherein calculating the Rice parameters for the TUs in the CTU based on the history counter comprises: calculating a local sum variable locSumAbs for a coefficient in a TU of the CTU using values of neighboring coefficients in a pre-determined neighborhood of the coefficient and the replacement variable HistValue; and deriving the Rice parameter for the TU based on the local sum variable locSumAbs.

12. The system of claim 11, wherein calculating a local sum variable locSumAbs for a coefficient in a TU of the CTU comprises: determining that a neighboring coefficient of a plurality of neighboring coefficients in the pre-determined neighborhood of the coefficient is outside the TU; and using the replacement variable HistValue as a value of the neighboring coefficient outside the TU to calculate the local sum variable locSumAbs.

13. The system of claim 8, wherein updating a replacement variable HistValue based on the history counter comprises updating the replacement variable HistValue for a color component cIdx by calculating: HistValue[cIdx] = 1 << StatCoeff[cIdx], wherein StatCoeff denotes the history counter.

14. A method for encoding a video, the method comprising: accessing a partition of the video, the partition comprising a plurality of coding tree units (CTUs); processing the partition of the video to generate a binary representation of the partition, the processing comprising: encoding each CTU of the plurality of CTUs in the partition, encoding the CTU comprising: updating a history counter StatCoeff for a color component for calculating Rice parameters; prior to calculating a next Rice parameter, updating a replacement variable HistValue based on the updated history counter; calculating the Rice parameters for transform units (TUs) in the CTU based on the updated replacement variable HistValue; and encoding coefficient values of the TUs into a binary representation corresponding to the TUs in the CTU based on the calculated Rice parameters; and encoding the binary representation of the partition into a bitstream of the video.

15. The method of claim 14, wherein updating the history counter StatCoeff comprises: in response to determining that a first non-zero Golomb-Rice coded transform coefficient in a TU is coded as abs_remainder, updating the history counter StatCoeff for a color component cIdx as:

StatCoeff[cIdx] = Floor(Log2(abs_remainder[cIdx])) + 1; and in response to determining that the first non-zero Golomb-Rice coded transform coefficient in the TU is coded as dec_abs_level, updating the history counter for a color component cIdx as:

StatCoeff[cIdx] = Floor(Log2(dec_abs_level[cIdx])), wherein Floor(x) represents the largest integer less than or equal to x, and Log 2(x) is base-2 logarithm of x.

16. The method of claim 14, wherein the partition is a frame, a slice, or a tile.

17. The method of claim 14, further comprising setting the history counter StatCoeff to an initial value based on a bit depth of samples of luma and chroma arrays of the video.

18. The method of claim 14, wherein calculating the Rice parameters for the TUs in the CTU based

on the history counter comprises: calculating a local sum variable locSumAbs for a coefficient in a TU of the CTU using values of neighboring coefficients in a pre-determined neighborhood of the coefficient and the replacement variable HistValue; and deriving the Rice parameter for the TU based on the local sum variable locSumAbs.

19. The method of claim 18, wherein calculating a local sum variable locSumAbs for a coefficient in a TU of the CTU comprises: determining that a neighboring coefficient of a plurality of neighboring coefficients in the pre-determined neighborhood of the coefficient is outside the TU; and using the replacement variable HistValue as a value of the neighboring coefficient outside the TU to calculate the local sum variable locSumAbs.

20. The method of claim 14, wherein updating a replacement variable HistValue based on the history counter comprises updating the replacement variable HistValue for a color component cIdx by calculating: $\text{HistValue}[\text{cIdx}] = 1 \ll \text{StatCoeff}[\text{cIdx}]$, wherein StatCoeff denotes the history counter.
