

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12404995
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Xiao; Juncheng et al.

Backlight module and display device

Abstract

The present application provides a backlight module and a display device. The backlight module includes: a metal layer including signal lines and first signal connection lines extending along a first direction in the same layer; and light-emitting control structures. One signal line is disposed at each of at least one side of each column of the light-emitting control structures, each light-emitting control structure is connected to the corresponding signal line, and any two adjacent ones of the light-emitting control structures in each column of the light-emitting control structures are connected through one first signal connection line.

Inventors:	Xiao; Juncheng (Shenzhen, CN), Li; Yan (Shenzhen, CN), Zhao; Bin (Shenzhen, CN), Li; Ji (Shenzhen, CN)
Applicant:	TCL CHINA STAR OPTOELECTRONICS TECHNOLOGY CO., LTD. (Shenzhen, CN)
Family ID:	75988501
Assignee:	TCL CHINA STAR OPTOELECTRONICS TECHNOLOGY CO., LTD. (Shenzhen, CN)
Appl. No.:	17/290068
Filed (or PCT Filed):	March 15, 2021
PCT No.:	PCT/CN2021/080715
PCT Pub. No.:	WO2022/170657
PCT Pub. Date:	August 18, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230139020 A1	May. 04, 2023

Foreign Application Priority Data

CN

202110185277.6

Feb. 10, 2021

Publication Classification

Int. Cl.: H01L25/075 (20060101); F21V23/00 (20150101); G09G3/34 (20060101); F21Y115/10 (20160101)

U.S. Cl.:

CPC F21V23/005 (20130101); G09G3/3426 (20130101); H01L25/0753 (20130101); F21Y2115/10 (20160801); G09G2300/0426 (20130101); H05K2201/10106 (20130101)

Field of Classification Search

CPC: F21V (23/005); G09G (3/3426); G09G (2300/0426); H01L (25/0753); F21Y (2115/10); H05K (2201/10106)

USPC: 257/88

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
11335244	12/2021	Wang	N/A	G09G 3/32
2020/0257167	12/2019	Miyata	N/A	G09G 3/3413

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
108287436	12/2017	CN	N/A
108447887	12/2017	CN	N/A
109116626	12/2018	CN	N/A
111540764	12/2019	CN	N/A
111752407	12/2019	CN	N/A
111968566	12/2019	CN	N/A
112230471	12/2020	CN	N/A
2018176656	12/2017	WO	N/A
2020001357	12/2019	WO	N/A

Primary Examiner: Nadav; Ori

Attorney, Agent or Firm: The Roy Gross Law Firm, LLC

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS

(1) This application is a National Phase of PCT Patent Application No. PCT/CN2021/080715

having International filing date of Mar. 15, 2021, which claims the benefit of priority of Chinese Application No. 202110185277.6 filed Feb. 10, 2021. The contents of the above applications are all incorporated by reference as if fully set forth herein in their entirety.

FIELD OF DISCLOSURE

(2) The present application relates to a field of display technology and in particular, to a backlight module and a display device.

DESCRIPTION OF RELATED ART

(3) Micro-LED is one of the most promising technologies among the display technologies for the next generation. Compared with current LCD and OLED display devices, micro-LED has the advantages of fast response time, wide color gamut, high resolution (i.e., PPI, measured in pixel per inch), and low power consumption. However, micro-LED involves many difficult and complicated techniques. Especially, bottlenecks occur when to realize mass transfer of the micro-LED key technology and to miniaturize LED particles. By contrast, as a combination of micro-LED and a backplane, mini-LED has a high contrast ratio, high color rendering performance, and other characteristics comparable to OLED, and a manufacturing cost of mini-LED is slightly higher than LCD and is only about 60% of the cost of the OLED, which makes mini-LED easier to implement than micro-LED and OLED. Therefore, there has been a trend for major panel manufacturers to develop mini-LED.

(4) However, lines connected to a driving circuit board (FPC) in a conventional mini-LED product are arranged as a network structure. To avoid short circuits between different lines, it is necessary to have multiple metal layers so that different lines can be designed in different metal layers, which results in a complex wiring design, and the design of multiple metal layers affects product yield and increases costs.

SUMMARY

(5) The embodiments of the present application provide a backlight module and a display device, which can simplify the wiring design, improve the product yield, and reduce the costs.

(6) A backlight module is provided according to one embodiment of the present application, comprising:

(7) a substrate;

(8) a metal layer disposed on the substrate, the metal layer comprising a plurality of signal lines and a plurality of first signal connection lines extending along a first direction, wherein the signal lines and the first signal connection lines are arranged in a same layer; and

(9) a plurality of light-emitting control structures disposed on the metal layer and arranged in a plurality of columns, wherein one of the signal lines is disposed at each of at least one side of each column of the light-emitting control structures, each of the light-emitting control structures in each column of the light-emitting control structures is connected to a corresponding one of the signal lines, and any two adjacent ones of the light-emitting control structures in each column of the light-emitting control structures are connected through one of the first signal connection lines.

(10) In one preferable embodiment, one of the signal lines is arranged at one side of each column of the light-emitting control structures; or two of the signal lines are disposed at two sides of each column of the light-emitting control structure; or one of the signal lines is arranged between each two columns of the light-emitting control structures; or one of the signal lines is arranged between any two adjacent columns of the light-emitting control structures.

(11) In one preferable embodiment, each of the light-emitting control structures comprises a controller and at least one light-emitting unit; and each of the controllers in each column of the light-emitting control structures and the corresponding signal line are electrically connected to the corresponding at least one light-emitting unit, and any two adjacent ones of the controllers in each column of the light-emitting control structures are electrically connected through one of the first signal connection lines.

(12) In one preferable embodiment, the metal layer further comprises a plurality of second signal

connection lines extending along the first direction, and the second signal connection lines are arranged in the same layer as the signal lines and the first signal connection lines; and each of the controllers and the corresponding at least one light-emitting unit are electrically connected to a corresponding one of the second signal connection lines.

(13) In one preferable embodiment, the controller and the corresponding at least one light-emitting unit are arranged along a second direction, the second signal connection line is arranged between the controller and the at least one light-emitting unit, and the at least one light-emitting unit is arranged between the controller and the corresponding signal line; or the controller and the corresponding at least one light-emitting unit are arranged along the first direction, and the second signal connection line is arranged at one side of the at least one light-emitting unit away from the corresponding signal line.

(14) In one preferable embodiment, each of the light-emitting units comprises a plurality of LED lamps arranged in at least one row along the second direction; and the LED lamps of each row in the light-emitting unit are connected in series, one end of each row of the LED lamps connected in series is electrically connected to the corresponding second signal connection line, and another end of each row of the LED lamps is electrically connected to the corresponding signal line.

(15) In one preferable embodiment, the metal layer further comprises a plurality of transmission lines extending along the first direction, the controllers in each column of the light-emitting control structures constitute a column of the controllers, and each of the controllers in each column of the controllers is connected to a corresponding one of the transmission lines; and one of the transmission lines is disposed at one side of each column of the controllers and arranged away from the corresponding signal line, and/or at least one of the transmission lines is arranged between each column of the controllers and the substrate.

(16) In one preferable embodiment, the transmission lines comprise at least one type of transmission lines, and each column of the controllers is correspondingly connected to the same type of transmission lines.

(17) In one preferable embodiment, the backlight module further comprises a first conductive structure, and the signal lines are electrically connected through the first conductive structure.

(18) In one preferable embodiment, the metal layer further comprises a first wiring connection line extending in a second direction, and the first conductive structure is the first wiring connection line; and the first wiring connection line is arranged at one end of each of the signal lines and is connected to the signal lines.

(19) In one preferable embodiment, the first conductive structure is a second wiring connection line disposed on a back side of the substrate; the signal lines extend along a side surface of the substrate to the back side of the substrate and are connected to the second wiring connection line; or the signal lines penetrate through the substrate and are connected to the second wiring connection line.

(20) In one preferable embodiment, the backlight module further comprises a first driving structure, and the first driving structure is connected with one end of each of the signal lines and one end of each column of the light-emitting control structures; and when the first conductive structure and the first driving structure are disposed on a same side of the substrate and arranged at a same end of the signal lines, the first conductive structure is disposed between the first driving structure and the substrate, or the first conductive structure is disposed at one side of the first driving structure away from the signal lines.

(21) In one preferable embodiment, the backlight module further comprises a first driving structure, the first driving structure is connected with one end of each of the signal lines and one end of each column of the light-emitting control structures, and the first conductive structure is a third wiring connection line disposed on the first driving structure; and the signal lines extend to the first driving structure and are connected to the third wiring connection line.

(22) In one preferable embodiment, the first driving structure comprises a first driving circuit board and a second driving circuit board, and the third wiring connection line comprises a first connection

sub-line disposed on the first driving circuit board and a second connection sub-line disposed on the second driving circuit board; and the signal lines comprise a plurality of first signal lines and a plurality of second signal lines, the first signal lines extend to the first driving circuit board and are connected to the first connection sub-line, and the second signal lines extend to the second driving circuit board and are connected to the second connection sub-line.

(23) In one preferable embodiment, the backlight module further comprises a second driving structure, the second driving structure is disposed at one end of each of the signal lines, and the first conductive structure is a fourth wiring connection line disposed on the second driving structure; and the signal lines extend to the second driving structure and are connected to the fourth wiring connection line.

(24) In one preferable embodiment, the second driving structure comprises a third driving circuit board and a fourth driving circuit board, and the fourth wiring connection line comprises a third connection sub-line disposed on the third driving circuit board and a fourth connection sub-line disposed on the fourth driving circuit board; and the signal lines comprise a plurality of third signal lines and a plurality of fourth signal lines, the third signal lines extend to the third driving circuit board and are connected to the third connection sub-line, and the fourth signal lines extend to the fourth driving circuit board and are connected to the fourth connection sub-line.

(25) In one preferable embodiment, the first conductive structure is a first conductive layer disposed on a side surface of the substrate; and the signal lines extend to the side surface of the substrate and are connected to the first conductive layer.

(26) In one preferable embodiment, the first conductive structure is a third conductive layer disposed on a back side of the substrate; and the third conductive layer passes through the substrate to be connected to the signal lines.

(27) In one preferable embodiment, the second conductive layer comprises a plurality of conductive lines; and each of the conductive lines penetrates through the dielectric layer to be connected to the signal lines.

(28) In one preferable embodiment, the dielectric layer is an insulating layer, and the second conductive layer completely covers the insulating layer.

(29) In one preferable embodiment, the first conductive structure is a third conductive layer disposed on a back side of the substrate; and the third conductive layer passes through the substrate to be connected to the signal lines.

(30) In one preferable embodiment, the backlight module further comprises a second conductive structure, and the transmission lines of the same type are electrically connected through the second conductive structure.

(31) The present application further provides a display device, comprising a display panel and the backlight module mentioned above, wherein the display panel is disposed on the backlight module.

(32) A metal layer is disposed on a substrate. The metal layer comprises a plurality of signal lines and a plurality of first signal connection lines extending along a first direction. The signal lines and the first signal connection lines are arranged in the same layer. One signal line is disposed at each of at least one side of each column of light-emitting control structures. Each light-emitting control structure in each column of the light-emitting control structures is connected to the corresponding signal line, and any two adjacent light-emitting control structures in each column of the light-emitting control structures are connected by one first signal connection line to simplify a wiring design and ensure that the lines are located in the same metal layer, thus improving the product yield and reducing the cost.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) The present application is described in detail below in conjunction with the accompanying drawings for ease of understanding the technical solutions and other beneficial effects of the present application.
- (2) FIG. 1 is a schematic cross-sectional view of a backlight module according to one embodiment of the present application;
- (3) FIG. 2 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (4) FIG. 3 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (5) FIG. 4 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (6) FIG. 5 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (7) FIG. 6 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (8) FIG. 7 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (9) FIG. 8 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (10) FIG. 9 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (11) FIG. 10 is a schematic view illustrating a light-emitting control structure in the backlight module according to one embodiment of the present application;
- (12) FIG. 11 is a schematic view illustrating the light-emitting control structure in the backlight module according to one embodiment of the present application;
- (13) FIG. 12 is a schematic view illustrating the light-emitting control structure in the backlight module according to one embodiment of the present application;
- (14) FIG. 13 is a schematic view illustrating the light-emitting control structure in the backlight module according to one embodiment of the present application;
- (15) FIG. 14 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (16) FIG. 15 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (17) FIG. 16 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (18) FIG. 17 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (19) FIG. 18 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (20) FIG. 19 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (21) FIG. 20 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (22) FIG. 21 is a schematic structural view illustrating the backlight module according to one embodiment of the present application;
- (23) FIG. 22 is a schematic structural view of the backlight module according to one embodiment of the present application;
- (24) FIG. 23 is a schematic cross-sectional view of the backlight module according to one

embodiment of the present application;

(25) FIG. 24 is a schematic structural view illustrating the backlight module according to one embodiment of the present application;

(26) FIG. 25 is a schematic structural view illustrating the backlight module according to one embodiment of the present application;

(27) FIG. 26 is a schematic cross-sectional view of the backlight module according to one embodiment of the present application;

(28) FIG. 27 is a schematic structural view illustrating the backlight module according to one embodiment of the present application;

(29) FIG. 28 is a schematic structural view illustrating a display device according to one embodiment of the present application; and

(30) FIG. 29 is a schematic partial cross-sectional view of the backlight module according to one embodiment of the present application.

DETAILED DESCRIPTION OF EMBODIMENTS

(31) The specific structure and functional details disclosed herein are only representative examples, and are used for the purpose of describing exemplary embodiments of the present application. However, the present application can be embodied in many alternative forms, and should not be construed as being limited only to the embodiments set forth herein.

(32) In the description of the present application, it should be understood that directional terms, such as “center”, “lateral”, “upper”, “lower”, “left”, “right”, “vertical”, “horizontal”, “top”, “bottom”, “inner”, and “outer”, are for the convenience of describing the application and simplifying the description based on the orientation or positional relationship shown in the drawings. The directional terms do not indicate or imply that the device or the element must have a specific orientation, be constructed and operated in a specific orientation, and therefore cannot be construed as a limitation of the present application. In addition, the terms “first” and “second” are for illustrative purposes only, and cannot be interpreted to indicate or imply relative importance or implicitly indicate the number of indicated technical features. Thus, the features defined with “first” and “second” may explicitly or implicitly include one or more of these features. In the description of the present application, unless otherwise specified, “multiple” means two or more. In addition, the term “comprising” and any variations thereof is intended to cover non-exclusive inclusion.

(33) In the description of the present application, it should be noted that, unless otherwise clearly specified and limited, the terms “installed”, “connected”, and “coupled” should be understood in a broad sense. For example, elements can be a fixedly connected, or detachably connected, or integrally connected; elements can be mechanically connected or electrically connected; elements can be directly connected or indirectly connected through an intermediate medium, and internal spaces of two elements can communicate with each other. For those of ordinary skill in the art, the specific meanings of the above-mentioned terms in this present application can be understood on a case-by-case basis.

(34) The terms used herein are only for describing specific embodiments and are not intended to limit the example embodiments. Unless the context clearly indicates otherwise, the singular forms “a” and “one” used herein are also intended to include the plural forms. It should also be understood that the terms “including” and/or “comprising” used herein specify the presence of the stated features, integers, steps, operations, units and/or components, and do not exclude the presence or addition of one or more other features, integers, steps, operations, units, components, and/or combinations thereof.

(35) The present application is further described below in conjunction with the accompanying drawings and embodiments.

(36) As shown in FIG. 1, one embodiment of the present application provides a backlight module, which includes a substrate 2, a metal layer 3 and a plurality of light-emitting control structures 4.

The metal layer 3 is disposed on the substrate 2, the light-emitting control structures 4 are disposed on the metal layer 3, and the light-emitting control structures 4 are arranged in a plurality of columns, as shown in FIGS. 2 to 8. Each column of the light-emitting control structures 4 is arranged along a first direction, and the first direction can be a vertical direction, a horizontal direction, or an oblique direction. Each column of the light-emitting control structures 4 can include one light-emitting control structure 4, or multiple (two or more) light-emitting control structures 4, the number of light-emitting control structures 4 in different columns can be the same or different, and the light-emitting control structures 4 in different columns can be arranged side by side or staggered; and the present application is not limited in this regard.

(37) For example, the first direction A is a vertical direction. As shown in FIG. 2, the light-emitting control structures 4 are arranged in columns, and the light-emitting control structures 4 in different columns are different in number. As shown in FIGS. 3 to 8, the light-emitting control structures 4 are arranged in multiple rows and multiple columns, and the light-emitting control structures 4 in different columns are the same in number.

(38) The metal layer 3 comprises a plurality of signal lines 31, and one of the signal lines 31 is disposed on each of at least one side of each column of the light-emitting control structures 4.

(39) For example, as shown in FIGS. 2 to 4, one of the signal lines 31 is arranged at each side of each column of the light-emitting control structures 4. Alternatively, as shown in FIG. 7, two signal lines 31 are respectively disposed at two sides of each column of the light-emitting control structures 4. Alternatively, as shown in FIG. 5 and FIG. 6, when there are multiple columns of the light-emitting control structures 4, one of the signal lines 31 is disposed between each two columns of the light-emitting control structures 4, so that one pair of the light-emitting control structures 4 is a group, and each group shares the same signal line 31. Alternatively, as shown in FIG. 8, one of the signal lines 31 is disposed between any two adjacent columns of the light-emitting control structures 4, so that any two adjacent columns of the light-emitting control structures 4 share one signal line 31. The signal lines 31 extend along the first direction A, and an extending length of the signal line 31 can be greater than or equal to a length of a column of the light-emitting control structures 4, so that each light-emitting control structure 4 in each column of the light-emitting control structures 4 can be connected to the corresponding signal line 31 by a shortest distance or no distance.

(40) As shown in FIGS. 4 to 9, the backlight module also includes a first driving structure 1. The first driving structure 1 can be disposed on a front side (i.e., one side of the substrate 2 close to the metal layer 3) of the substrate 2, and the first driving structure 1 can also be disposed on a back side (i.e., one side of the substrate 2 away from the metal layer 3) of the substrate 2.

(41) One end of each signal line 31 is connected to the first driving structure 1, so that the first driving structure 1 is electrically connected to one end of each light-emitting control structure 4 through the signal line 31, and thereby the first driving structure 1 transmits signals to each light-emitting control structure 4.

(42) When the first driving structure 1 is disposed on the front side of the substrate 2, as shown in FIGS. 5 to 8, the first driving structure 1 can be arranged in the extending direction of the signal line 31, and each signal line 31 can extend along the first direction A to the first driving structure 1 and is connected to the first driving structure 1. Alternatively, as shown in FIG. 4, the first driving structure 1 is not arranged in the extending direction of the signal lines 31, and each signal line 31 first extends along the first direction A, and then extends along a second direction B to the first driving structure 1 to be connected to the first driving structure 1. The second direction B can be perpendicular to the first direction A. In other embodiments, the second direction B can also be inclined relative to the first direction A. When the first driving structure 1 is disposed on the back side of the substrate 2, as shown in FIG. 9, the signal line 31 can extend to the back side of the substrate 2 through a side surface of the substrate 2 to be connected to the first driving structure 1, or the signal line 31 can penetrate through the substrate 2 to be connected to the first driving

structure **1**.

(43) The metal layer **3** further comprises a plurality of first signal connection lines **32**, and the first signal connection lines **32** and the signal lines **31** are arranged in the same layer. When a column of the light-emitting control structures **4** comprises multiple light-emitting control structures **4**, any two adjacent light-emitting control structures **4** in the column of the light-emitting control structures **4** are connected by one first signal connection line **32**, and the light-emitting control structure **4** closest to the first driving structure **1** in this column of the light-emitting control structures **4** can be connected to the first driving structure **1** through one of the first signal connection lines **32**. When one column of the light-emitting control structures **4** comprises only one of the light-emitting control structures **4**, the light-emitting control structure **4** in this column of the light-emitting control structures **4** can be directly connected to the first driving structure **1** through one first signal connection line **32**, as shown in FIG. 2. The first signal connection lines **32** are parallel to and spaced from the signal lines **31**, that is, the first signal connection lines **32** extend along the first direction A. The first driving structure **1** can transmit signals to each light-emitting control structure **4** through the first signal connection line **32**.

(44) To be specific, when the first driving structure **1** is disposed on the front side of the substrate **2**, the first signal connection lines **32** connected to the first driving structure **1** can extend to the first driving structure **1** along the first direction A, or the first signal connection lines **32** connected to the first driving structure **1** can first extend along the first direction A and then extend along the second direction B to the first driving structure **1**. When the first driving structure **1** is disposed on the back side of the substrate **2**, as shown in FIG. 9, the first signal connection lines **32** connected to the first driving structure **1** can extend through the side surface of the substrate **2** to the first driving structure on the back side of the substrate **2**, or the first signal connection lines **32** connected to the first driving structure **1** directly penetrate through the substrate **2**.

(45) Furthermore, as shown in FIGS. 2 to 8, each light-emitting control structure **4** comprises a controller **41** and at least one light-emitting unit **42**. Each controller **41** in each column of the light-emitting control structures **4** and the corresponding signal line **31** are electrically connected to the at least one light-emitting unit **42**. When one column of the light-emitting control structures **4** comprises multiple light-emitting control structures **4**, any adjacent two controllers **41** in this column of the light-emitting control structures **4** are connected by one of the first signal connection lines **32**, and the controller **41** closest to the first driving structure **1** in this column of the light-emitting control structures **4** is connected to the first driving structure **1** through one of the first signal connection lines **32**. When one column of the light-emitting control structures **4** comprises only one light-emitting control structure **4**, the controller **41** in this column of the light-emitting control structures **4** can be directly connected to the first driving structure **1** through one of the first signal connection lines **32**, so that the first driving structure **1** can transmit signals to the controller **41**, and then drive the corresponding light-emitting unit **42** through the controller **41**.

(46) Furthermore, as shown in FIGS. 10 to 13, the metal layer **3** further comprises a plurality of second signal connection lines **33** extending along the first direction A. The second signal connection lines **33** and the first signal connection lines **32** are arranged in the same layer as the signal lines **31**. Each controller **41** and its corresponding light-emitting unit **42** are electrically connected to one of the second signal connection lines **33**.

(47) Each light-emitting unit **42** comprises a plurality of LED lamps **43** arranged in at least one row along the second direction B, and the second direction B and the first direction A can intersect or be perpendicular to each other. When the number of the LED lamps in one row is multiple, the LED lamps **43** in this row are connected in series and connected between the corresponding second signal connection line **33** and the corresponding signal line **31**. When the number of the LED lamps **43** in one row is one, the LED lamp in this row is directly connected between the corresponding second signal connection line **33** and the corresponding signal line **31**.

(48) As shown in FIGS. 10 to 13, one light-emitting unit **42** can comprise sixteen LED lamps **43**

distributed in four rows and four columns. The LED lamps **43** of each row in the light-emitting unit **42** are connected in series, and the LED lamps **43** of different rows are connected in parallel. That is to say, one end of each row of serially connected LED lamps **43** is electrically connected to the second signal connection line **33**, and another end of each row of serially connected LED lamps **43** is electrically connected to the corresponding signal line **31**. Wherein, an extending length of the second signal connection line **33** can be equal to a length of one column of the LED lamps **43** in the light-emitting unit **42** to ensure that each row of the LED lamps **43** in the light-emitting unit **42** can be electrically connected to the corresponding second signal connection line **33** by a shortest distance or no distance, thus reducing a space occupied by the second signal connection line **33**. In the present embodiment, different rows of the LED lamps **43** in the light-emitting unit **42** are connected in parallel to ensure that if a certain LED lamp is damaged, it only causes the LED lamps of the row where the damaged LED lamp is located to go off, without affecting all the LED lamps of the light-emitting unit. By adjusting the brightness of other rows of the LED lamps in the light-emitting unit (the brightness can be adjusted by, for example, increasing a driving current), it can be ensured that the overall brightness of the light-emitting unit **42** is not affected, and the overall product yield is improved.

(49) The controller **41**, the corresponding light-emitting unit **42**, and the corresponding second signal connection line **33** can have various positional relationships. If one signal line **31** is disposed at any side of one column of the light-emitting control structures **4**, or one signal line **31** is arranged between every two columns of the light-emitting control structures **4**, the controller and the corresponding at least one light-emitting unit **42** can be arranged along the first direction A or along the second direction B.

(50) For example, as shown in FIG. **10**, the controller **41** and the corresponding light-emitting unit **42** can be distributed along the second direction B (if the controller **41** is arranged corresponding to multiple light-emitting units **42**, the multiple light-emitting units **42** can be distributed along the first direction A). The second signal connection line **33** is disposed between the corresponding controller **41** and the corresponding light-emitting unit **42**, and the light-emitting unit **42** is disposed between the corresponding controller **41** and the corresponding signal line **31**.

Alternatively, the second signal connection line **33** is disposed at one side of the corresponding light-emitting unit **42** away from the corresponding signal line **31**, and the controller **41** is disposed between the corresponding light-emitting unit **42** and the corresponding signal line **31**.

(51) In another example, as shown in FIG. **11**, the controller **41** and the corresponding at least one light-emitting unit **42** can be distributed along the first direction A, and the second signal connection line **33** is disposed at one side of the corresponding light-emitting unit **42** and arranged away from the signal line **31**.

(52) When the light-emitting unit **42** comprises multiple rows of the LED lamps **43**, the controller **41** can also be located between the multiple rows of the LED lamps **43** of the light-emitting unit **42**, as shown in FIG. **12**.

(53) If two signal lines **31** are disposed at two sides of one column of the light-emitting control structures **4**, one second signal connection line **33** is correspondingly disposed between the controller **41** and each signal line **31**, and at least one light-emitting unit **42** arranged along the first direction A is disposed between each second signal connection line **33** and the corresponding signal line **31**, as shown in FIG. **13**.

(54) As shown in FIGS. **2** to **8**, the metal layer **3** can also comprise a plurality of transmission lines **34** extending along the first direction A. That is to say, the transmission lines **34**, the signal lines **31**, and the first signal connection lines **32**, the second signal connection lines **33** are all arranged in the same layer and are parallel and spaced apart from each other. The controllers **41** in each column of the light-emitting control structures **4** constitute a column of the controllers **41**, and one transmission line **34** is arranged at one side of each column of the controllers **41** and disposed away from the corresponding signal line **31**, and/or at least one transmission line **34** can be

correspondingly disposed between each column of the controllers **41** and the substrate **2**, that is, at least one transmission line **34** can be disposed directly under each column of the controllers **41**. Each controller **41** in each column of the controllers **41** is connected to the corresponding transmission line **34**, and one end of each transmission line **34** is connected to the first driving structure **1**, so that the first driving structure **1** transmits signals to the controller **41** through the transmission line **34**.

(55) Specifically, when the first driving structure **1** is located on the front side of the substrate, the transmission line **34** can extend to the first driving structure **1** along the first direction A and be connected to the first driving structure **1**. Alternatively, the transmission line **34** can first extend along the first direction A, and then extend along the second direction B to the first driving structure **1** to be connected to the first driving structure **1**. When the first driving structure **1** is located on the back side of the substrate **2**, the transmission line **34** can extend to the back side of the substrate **2** through the side surface of the substrate **2** to be connected to the first driving structure **1**. Alternatively, the transmission line **34** penetrates through the substrate **2** to be connected to the first driving structure **1**.

(56) The transmission lines **34** can comprise at least one type of transmission line, and different types of transmission lines transmit different signals. Each column of the controllers **41** is disposed corresponding to one transmission line of the same type, that is, each column of the controllers **41** is connected to only one transmission line of the same type, but each column of the controllers **41** can be connected to different types of transmission lines. Therefore, when there are multiple transmission lines **34** disposed between each column of the controllers **41** and the substrate **2**, the transmission lines **34** are different types of transmission lines, and the transmission lines **34** are arranged at intervals.

(57) The transmission lines **34** can comprise a plurality of first-type transmission lines, that is, a plurality of transmission lines **34a**. Each column of the controllers **41** can be arranged corresponding to one transmission line **34a**, and each controller **41** in each column of the controllers **41** is connected to the corresponding transmission line **34a**, and one end of each transmission line **34a** is connected to the first driving structure **1**.

(58) The transmission lines **34** can also comprise a plurality of second-type transmission lines, that is, a plurality of transmission lines **34b**. Each column of the controllers **41** can be arranged corresponding to one transmission line **34b**, and each controller **41** in each column of the controllers **41** is connected to the corresponding transmission line **34b**, and one end of each transmission line **34b** is connected to the first driving structure **1**.

(59) When the plurality of transmission lines **34** comprise the plurality of transmission lines **34a**, the transmission line **34a** arranged corresponding to each column of the controllers **41** can be disposed at one side of the column of the controllers **41** and arranged away from the corresponding signal line **31**. To be specific, each column of the controllers **41** can be connected to one transmission line **34a**, as shown in FIG. 2 and FIG. 3. Alternatively, one transmission line **34a** can be correspondingly disposed between each two columns of the controllers **41**, that is, two columns of the controllers **41** share one transmission line **34a**, as shown in FIG. 5. The transmission line **34a** arranged corresponding to each column of the controllers **41** can also be located directly under the column of the controllers **41**, as shown in FIGS. 4 and 6 to 8.

(60) When the plurality of transmission lines **34** further comprises the plurality of transmission lines **34b**, the transmission line **34b** arranged corresponding to each column of the controllers **41** can be disposed directly under the column of the controllers **41**. Alternatively, when the transmission line **34a** arranged corresponding to each column of the controllers **41** is located directly below the column of the controllers **41**, the transmission line **34a** arranged corresponding to each column of the controllers **41** can also be located at one side of the column of the controllers **41** away from the corresponding signal line **31**.

(61) The transmission line **34a** can be a GND line, and the transmission line **34b** can be a voltage

line for providing an operating voltage to the controller; or the transmission line **34a** can be a voltage line, and the transmission line **34b** can be a GND line.

(62) In the present embodiment, the signal lines **31**, the first signal connection lines **32**, the second signal connection lines **33**, and the transmission lines **34** can all be arranged in the same metal layer **3**. The different lines are arranged in parallel and spaced apart to avoid network structure wiring, thereby simplifying the wiring design, improving the product yield, and reduces the cost.

(63) A voltage delivered in the signal line **31** is relatively high, and therefore, in order to avoid a transmission loss, the signal lines **31** are electrically connected through a first conductive structure to ensure in-plane voltage balance. The signal lines **31** that are electrically connected can be arranged according to actual needs. It is not necessary to electrically connect all the signal lines **31**, that is, a portion of the signal lines **31** are electrically connected through the first conductive structure, and a portion of the signal lines **31** are not electrically connected through the first conductive structure.

(64) In a first embodiment, the metal layer **3** further comprises a first wiring connection line **51** extending along the second direction B, the first conductive structure is the first wiring connection line **51**, and the first wiring connection line **51** is located at one end of each of the signal lines **31** and is connected to the signal lines **31**.

(65) As shown in FIG. **14**, the first wiring connection line **51** can be disposed at one end of each of the signal line **31** that is not connected to the first driving structure **1**, that is, the first wiring connection line **51** is located at one end of each of the signal line **31** away from the first driving structure **1**. The signal lines **31** extend along the first direction A to the first wiring connection line **51**, and are connected to the first wiring connection line **51**. The first driving structure **1** can be disposed on the front side of the substrate **2** or on the back side of the substrate **2**.

(66) As shown in FIG. **15**, the first wiring connection line **51** can also be disposed at one end of each of the signal lines **31**, which is connected to the first driving structure **1**, that is, the first wiring connection line **51** is disposed at one end of each of the signal lines **31** close to the first driving structure **1**. The signal lines **31** extend along the first direction A to the first wiring connection line **51**, and are connected to the first wiring connection line **51**. Other lines, such as the first signal connection lines **32**, the transmission line **34**, also need to be connected to the first driving structure **1**, and therefore, in order to avoid other lines being connected to the first wiring connection line **51**, the first driving structure **1** can be set on the front side of the substrate **2**, and the first wiring connection line **51** is arranged between the first driving structure **1** and the substrate **2** (that is, the first wiring connection line **51** can be arranged directly under the first driving structure **1**; however, the first driving structure **1** is not shown in FIG. **15**). Alternatively, the first wiring connection line **51** can be arranged at one side of the first driving structure **1** away from other lines, so that other lines do not need to extend to the first wiring connection line **51** to be connected to the first driving structure **1**, thus preventing other lines from contacting with the first wiring connection line **51**.

(67) In a second embodiment, the first conductive structure is a second wiring connection line **52** disposed at a bottom of the substrate **2**. The signal lines **31** extend along one side surface of the substrate **2** to the back side of the substrate **2** and are connected to the second wiring connection line **52**. Alternatively, the signal lines **31** penetrate through the substrate **2** and are connected to the second wiring connection line **52**.

(68) When the second wiring connection line **52** is disposed on the back side of the substrate **2**, the first driving structure **1** can be disposed on the front side of the substrate **2** or on the back side of the substrate **2**. When the first driving structure **1** is located on the back side of the substrate **2**, as shown in FIG. **16**, other lines, such as the first signal connection lines **32** and the transmission lines **34**, extend along the side surface of the substrate **2** to the back side of the substrate **2** to be connected to the first driving structure **1**. In order to prevent other lines from crossing the second wiring connection line **52**, the second wiring connection line **52** can be arranged between the first

driving structure **1** and the substrate **2** (that is, the second wiring connection line **52** can be arranged directly under the first driving structure **1**; however, the first driving structure is not illustrated in the FIG. **16**). Alternatively, the second wiring connection line **52** can be arranged at one side of the first driving structure **1** away from other lines, so that other lines do not need to extend to the second wiring connection line **52** to be connected to the first driving structure **1**, and thereby other lines are prevented from contacting with the first wiring connection line **51**.

(69) In a third embodiment, as shown in FIG. **17**, the first conductive structure is a third wiring connection line **53** disposed on the first driving structure **1**, and the signal lines **31** extend to the first driving structure **1** and are connected to the third wiring connection line **53**.

(70) As shown in FIG. **18**, the first driving structure **1** can comprise a first driving circuit board **11** and a second driving circuit board **12**, and the third wiring connection line **53** can comprise a first connection sub-line **531** disposed on the first driving circuit board **11** and a second connection sub-line **532** disposed on the second driving circuit board **12**. The signal lines **31** can comprise a plurality of first signal lines and a plurality of second signal lines. The first signal lines extend to the first driving circuit board **11** and are connected to the first connection sub-line **531**. The second signal lines extend to the second driving circuit board **12** and are connected to the second connection sub-line **532**. The number of the first signal lines connected to the first connection sub-line **531** can be equal to or different from the number of the second signal lines connected to the second connection sub-line **532**.

(71) In a fourth embodiment, as shown in FIG. **19**, the backlight module can further comprise a second driving structure **6**, and the second driving structure **6** can be disposed at one end of each of the signal lines **31**. For example, the second driving structure **6** can be disposed at one end of the signal lines **31** and away from the first driving structure **1**, and the first conductive structure is a fourth wiring connection line **54** disposed on the second driving structure **6**. The signal lines **31** extend to the second driving structure **6** and are connected to the fourth wiring connection line **54**.

(72) As shown in FIG. **20**, the second driving structure **6** can comprise a third driving circuit board **61** and a fourth driving circuit board **62**, and the fourth wiring connection line **54** can comprise a third connection sub-line **541** disposed on the third driving circuit board **61** and a fourth connection sub-line **542** disposed on the fourth driving circuit board **62**. The signal lines **31** can comprise a plurality of third signal lines and a plurality of fourth signal lines, and the third signal lines extend to the third driving circuit board **61** and are connected to the third connection sub-line **541**. The fourth signal lines extend to the fourth driving circuit board **62** and are connected to the fourth connection sub-line **542**. Wherein, the number of the third signal lines connected to the third connection sub-line **541** can be equal to or different from the number of the fourth signal lines connected to the fourth connection sub-line **542**.

(73) In a fifth embodiment, the first conductive structure is the first conductive layer **55** disposed on the side surface of the substrate **2**. The signal lines **31** extend to the side surface of the substrate **2** and are connected to the first conductive layer **55**. The first conductive layer **55** can be formed on the side surface of the substrate **2** by side deposition or metal casting. The first conductive layer **55** can be a silver adhesive, a conductive adhesive, or etc.

(74) As shown in FIG. **21**, the side surface of the substrate **2** can be a side surface close to one end of the signal lines **31** that is not connected to the first driving structure **1**. The signal lines **31** extend to the side surface along the first direction A, and are connected to the first conductive layer **55** on the side surface. The first driving structure **1** can be disposed on the front side of the substrate **2** or on the back side of the substrate **2**.

(75) As shown in FIG. **22**, the side surface of the substrate **2** can also be a side surface close to one end of the signal lines **31** connected to the first driving structure **1**. Other lines, such as the first signal connection lines **32** and the transmission lines **34**, also need to be connected to the first driving structure **1**, and therefore, in order to prevent other lines from being connected to the first conductive layer **55** on the side surface, the first driving structure **1** can be arranged on the front

side of the substrate 2, so that other lines can be connected to the first driving structure 1 without extending to the side surface, and other lines are prevented from contacting the first conductive layer 55 on the side surface. Each signal line 31 extends to the first driving structure 1, is connected to the first driving structure 1, and continues to extend from below the first driving structure 1 to the side surface, and is connected to the first conductive layer 55 on the side surface.

(76) In a sixth embodiment, as shown in FIG. 23, the backlight module further comprises a dielectric layer 7 disposed on the substrate 2 and the metal layer 3, and the first conductive structure is a second conductive layer 56 disposed on the dielectric layer 7. The second conductive layer 56 can penetrate through the dielectric layer 7 to be connected to the signal lines 31. To be specific, the dielectric layer 7 is provided with a plurality of first through holes 71, and the second conductive layer 56 is further extended and arranged in the first through holes 71 to be connected to the signal lines 31.

(77) An orthographic projection of the second conductive layer 56 projected on the metal layer 3 overlaps at least a portion of the signal lines 31, and the first through holes 71 are correspondingly arranged at positions where the second conductive layer 56 overlaps the signal lines, so as to ensure that the second conductive layer 56 is connected to the signal lines 31.

(78) The dielectric layer 7 can be black oil, white oil, a reflective sheet, an insulating layer, or etc. During production, the first through holes 71 are formed in the dielectric layer 7 through exposure and other processes. Then, in a later stage of a die bonding process, a conductive material is filled in the first through holes 71 and covers the dielectric layer 7 to form the second conductive layer 56. The conductive material can be solder.

(79) As shown in FIG. 24, the second conductive layer 56 can comprise a plurality of conductive lines 561, and the conductive lines 561 can penetrate through the dielectric layer 7 to be connected to the signal lines 31. An orthographic projection of each conductive line 561 projected on the metal layer 3 at least partially overlaps the signal lines 31, and the first through holes 71 are correspondingly arranged at positions where the conductive lines 561 overlap the signal lines 31, so as to ensure that the conductive lines 561 are connected to the signal lines 31. Different conductive lines 561 can be connected to the same or partially the same or completely different signal lines 31. By connecting the conductive lines 561 to the signal lines 31 at different positions, uniformity of the in-plane voltage is further improved.

(80) When the dielectric layer 7 is an insulating layer, the second conductive layer 56 can completely cover the insulating layer, as shown in FIG. 25. Coating an entire surface of the insulating layer with the second conductive layer 56 can not only improve the in-plane uniformity, but also shield signals and improve electromagnetic interference.

(81) In a seventh embodiment, as shown in FIG. 26, the first conductive structure is a third conductive layer 57 disposed on the back side of the substrate 2. The third conductive layer 57 can penetrate through the substrate 2 to be connected to the signal lines 31. To be specific, a plurality of second through holes 21 are defined in the substrate 2, and the third conductive layer 57 is further extended and disposed in the second through holes 21 to be connected to the signal lines 31.

(82) An orthographic projection of the third conductive layer 57 projected on the metal layer 3 at least partially overlaps the signal lines 31, and the second through holes 21 are correspondingly arranged at positions where the third conductive layer 57 and the signal lines 31 overlap, so as to ensure that the third conductive layer 57 is connected to the signal lines 31.

(83) As shown in FIG. 27, the third conductive layer 57 can comprise a plurality of conductive lines 571. The conductive lines can penetrate through the substrate 2 to be connected to the signal lines 31. In detail, an orthographic projection of each conductive line 571 projected on the metal layer 3 at least partially overlaps the signal lines 31, and the second through holes 21 are correspondingly arranged at positions where the conductive lines 571 and the signal lines 31 overlap, so as to ensure that the conductive lines 571 are extended in the second through holes 21 to be connected to the signal lines 31. Different conductive lines 571 can be connected to

completely the same, partially the same, or completely different signal lines **31**. By connecting the conductive lines **571** to the signal lines **31** at different positions, the uniformity of the in-plane voltage can be further improved.

(84) The transmission lines **34** also need to deliver voltage, and therefore, in order to avoid a transmission loss, the backlight module can further comprise a second conductive structure, and the same type of transmission lines in the transmission lines **34** can also be electrically connected through the second conductive structure to further ensure the balance of the in-plane voltage. The transmission lines **34** of the same type that are electrically connected can be arranged according to actual needs. It is not necessary to electrically connect all the transmission lines **34** of the same type. That is to say, a portion of the transmission lines **34** of the same type can be electrically connected through the second conductive structure, while some of the transmission lines of the same type are not electrically connected through the second conductive structure.

(85) The way that the transmission lines of the same type are connected through the second conductive structure is similar to the way that the signal lines **31** are connected through the first conductive structure. That is to say, the transmission lines of the same type can be connected through the above-mentioned seven embodiments. The seven embodiments of the signal lines **31** can collaborate freely with the seven embodiments of the transmission lines of the same type, as long as the connection between the signal lines **31** and the connection between the transmission lines of the same type do not cross.

(86) For example, the transmission lines of the first type, that is, the transmission lines **34a**, are electrically connected through the second conductive structure. As shown in FIG. **14**, the first conductive structure is the first wiring connection line **51** disposed at one end of the signal lines **31** away from the first driving structure **1**, the second conductive structure can be a wiring connection line **81** disposed on the first driving structure **1**, and the transmission lines **34a** extend to the first driving structure **1** and are connected to the wiring connection line **81**.

(87) As shown in FIG. **15**, the first conductive structure is the first wiring connection line **51** disposed at one end of the signal lines **31** close to the first driving structure **1**, and the second conductive structure can be a wiring connection line **82** disposed at one end of the signal lines **31** away from the first driving structure. The transmission lines **34a** extend to the wiring connection line **82** and are connected to the wiring connection line **82**.

(88) As shown in FIG. **17**, the first conductive structure is a third wiring connection line **53** disposed on the first driving structure **1**, and the second conductive structure can be a conductive layer **83** arranged on the side surface of the substrate **2** away from the first driving structure **1**. The transmission lines **34a** extend to the side surface and are connected to the conductive layer **83** disposed on the side surface.

(89) As shown in FIG. **18**, the first conductive structure comprises the first connection sub-line **531** disposed on the first driving circuit board **11** and the second connection sub-line **532** disposed on the second driving circuit board **12**. The second conductive structure can comprise a third connection sub-line **841** disposed on the third driving circuit board **61** and a fourth connection sub-line **842** disposed on the fourth driving circuit board **62**. A portion of the transmission lines **34a** extends to the third driving circuit board **61** and is connected to the third connection sub-line **841**, and a portion of the transmission wiring **34a** extend to the fourth driving circuit board **62** and are connected to the fourth connection sub-line **842**.

(90) As shown in FIG. **19**, the first conductive structure is the fourth wiring connection line **54** disposed on the second driving structure **6**, and the second conductive structure is a conductive layer **85** arranged on the side surface of the substrate **2** close to the first driving structure **1**. The transmission lines **34a** extend to the first driving structure **1**, are connected to the first driving structure **1**, and continue to extend from under the first driving structure **1** to the side surface of the substrate **2** to be connected to the conductive layer **85** on the side surface.

(91) In addition, the second conductive structure can also be a wiring connection line disposed on

the back side of the substrate **2**, or can be a conductive layer disposed on the dielectric layer **7**, or can be a conductive layer disposed on the back side of the substrate **2**; a detailed description thereof is omitted herein for brevity.

(92) In summary, in the present application, a metal layer **3** is disposed on a substrate. The metal layer **3** comprises a plurality of signal lines **31** and a plurality of first signal connection lines **32** extending along a first direction A. The signal lines **31** and the first signal connection lines **32** are arranged in the same layer. One signal line **31** is disposed at each of at least one side of each column of light-emitting control structures **4**. Each light-emitting control structure **4** in each column of the light-emitting control structures **4** is connected to the corresponding signal line **31**, and any two adjacent light-emitting control structures **4** in each column of the light-emitting control structures **4** are connected by one first signal connection line **32** to simplify a wiring design and ensure that the lines are located in the same metal layer, which improves the product yield and reduces the cost. The signal lines **31** are connected through the first conductive structure, and the transmission lines **34** are connected through the second conductive structure, so the uniformity of the in-plane voltage is effectively improved.

(93) As shown in FIG. **28**, one embodiment of the present application provides a display device. The display device comprises a display panel **100** and a backlight module **200**. The display panel **100** is disposed on the backlight module **200**, and the backlight module **200** is the backlight module in the above embodiments, so a detailed description thereof is not repeated herein for brevity.

(94) The display device provided by the present application can simplify the wiring design in the backlight module **200**, can ensure that the lines are located in the same metal layer, and can improve product yield and reduce costs. The signal lines in the backlight module **200** are connected through the first conductive structure, and the transmission lines of the same type are connected through the second conductive structure, thus effectively improving the uniformity of the in-plane voltage.

(95) In summary, although the application has been disclosed as above in preferable embodiments, the above-mentioned embodiments are not intended to limit the present application. Those of ordinary skill in the art can make various changes and modifications without departing from the spirit and scope of the present application, so the protection scope of the present application should be defined by the appended claims.

Claims

1. A backlight module, comprising: a substrate; a metal layer disposed on the substrate, the metal layer comprising a plurality of signal lines and a plurality of first signal connection lines extending along a first direction, wherein the signal lines and the first signal connection lines are horizontally aligned with each other on a same plane on a front side of the substrate and on a same plane on a back side of the substrate; and a plurality of light-emitting control structures disposed on the metal layer and arranged in a plurality of columns, wherein one of the signal lines is disposed on at least one side of each column of the light-emitting control structures, the light-emitting control structures in each column are connected to a corresponding one of the signal lines, and any two adjacent ones of the light-emitting control structures in each column of the light-emitting control structures are connected through one of the first signal connection lines, wherein each of the light-emitting control structures comprises a controller and at least one light-emitting unit, each of the controllers in each column of the light-emitting control structures and the corresponding signal line are electrically connected to the corresponding at least one light-emitting unit, all the controllers in each column of the light-emitting control structures are directly electrically connected to each other through a same-layer electrical connection path established by one of the first signal connection lines across each column of the light-emitting control structures, and the controllers are arranged on a same side in each column of the light-emitting control structures, wherein an orthographic

projection of the signal lines does not overlap with an orthographic projection of the light-emitting control structures on the substrate.

2. The backlight module according to claim 1, wherein one of the signal lines is arranged on one side of each column of the light-emitting control structures; or two of the signal lines are disposed on two sides of each column of the light-emitting control structure; or one of the signal lines is arranged between each two columns of the light-emitting control structures; or one of the signal lines is arranged between any two adjacent columns of the light-emitting control structures.

3. The backlight module according to claim 2, wherein the metal layer further comprises a plurality of second signal connection lines extending along the first direction, and the second signal connection lines are arranged in the same layer as the signal lines and the first signal connection lines; and each of the controllers and the corresponding at least one light-emitting unit are electrically connected to a corresponding one of the second signal connection lines.

4. The backlight module according to claim 3, wherein the controller and the at least one light-emitting unit are arranged along a second direction, the second signal connection line is arranged between the controller and the at least one light-emitting unit, and the at least one light-emitting unit is arranged between the controller and the corresponding signal line; or the controller and the at least one light-emitting unit are arranged along the first direction, and the corresponding second signal connection line is arranged at one side of the at least one light-emitting unit away from the corresponding signal line.

5. The backlight module according to claim 4, wherein each of the light-emitting units comprises a plurality of LED lamps arranged in at least one row along the second direction; and the LED lamps of each row in the light-emitting unit are connected in series, and one end of each row of the LED lamps connected in series is electrically connected to the corresponding second signal connection line, and the other end of each row of the LED lamps is electrically connected to the corresponding signal line.

6. The backlight module according to claim 3, wherein the metal layer further comprises a plurality of transmission lines extending along the first direction, the controllers in each column of the light-emitting control structures constitute a column of the controllers, and each of the controllers in each column of the controllers is connected to a corresponding one of the transmission lines; and one of the transmission lines is disposed at one side of each column of the controllers and arranged away from the corresponding signal line, and/or at least one of the transmission lines are arranged between each column of the controllers and the substrate.

7. The backlight module according to claim 1, wherein the backlight module further comprises a first conductive structure, and the signal lines are electrically connected through the first conductive structure.

8. The backlight module according to claim 7, wherein the metal layer further comprises a first wiring connection line extending in a second direction, and the first conductive structure is the first wiring connection line; and the first wiring connection line is arranged at one end of each of the signal lines and is connected to the signal lines.

9. The backlight module according to claim 7, wherein the first conductive structure is a second wiring connection line disposed on a back surface of the substrate; the signal lines extend along a side surface of the substrate to the back surface of the substrate and are connected to the second wiring connection line; or the signal lines pass through the substrate and are connected to the second wiring connection line.

10. The backlight module according to claim 8, wherein the backlight module further comprises a first driving structure, and the first driving structure is connected with one longitudinal end of each of the signal lines and one longitudinal end of each column of the light-emitting control structures; and when the first conductive structure and the first driving structure are disposed on a same side of the substrate and at a same end of the signal lines, the first conductive structure is located between the first driving structure and the substrate, or the first conductive structure is located at one side of

the first driving structure away from the signal lines.

11. The backlight module according to claim 7, wherein the backlight module further comprises a first driving structure, the first driving structure is connected with one end of each of the signal lines and one end of each column of the light-emitting control structures, and the first conductive structure is a third wiring connection line disposed on the first driving structure; and the signal lines extend to the first driving structure and are connected with the third wiring connection line.

12. The backlight module according to claim 11, wherein the first driving structure comprises a first driving circuit board and a second driving circuit board, and the third wiring connection line comprises a first connection sub-line disposed on the first driving circuit board and a second connection sub-line disposed on the second driving circuit board; and the signal lines comprise a plurality of first signal lines and a plurality of second signal lines, the first signal lines extend to the first driving circuit board and are connected to the first connection sub-line, and the second signal lines extend to the second driving circuit board and are connected with the second connection sub-line.

13. The backlight module according to claim 7, wherein the backlight module further comprises a second driving structure, the second driving structure is disposed at one end of each of the signal lines, and the first conductive structure is a fourth wiring connection line disposed on the second driving structure; and the signal lines extend to the second driving structure and are connected with the fourth wiring connection line.

14. The backlight module according to claim 13, wherein the second driving structure comprises a third driving circuit board and a fourth driving circuit board, the fourth wiring connection line comprises a third connection sub-line disposed on the third driving circuit board and a fourth connection sub-line disposed on the fourth driving circuit board; the signal lines comprise a plurality of third signal lines and a plurality of fourth signal lines, the third signal lines extend to the third driving circuit board and are connected with the third signal lines, and the fourth signal lines extend to the fourth driving circuit board and are connected with the fourth connection sub-line.

15. The backlight module according to claim 7, wherein the first conductive structure is a first conductive layer disposed on a side surface of the substrate; the signal lines extend to the side surface of the substrate and are connected to the first conductive layer; or the first conductive structure is a third conductive layer disposed on a back surface of the substrate; the third conductive layer passes through the substrate to be connected to the signal lines.

16. The backlight module according to claim 7, wherein the backlight module further comprises a dielectric layer disposed on the substrate and the metal layer, and the first conductive structure is a second conductive layer disposed on the dielectric layer; and the second conductive layer passes through the dielectric layer to be connected to the signal lines.

17. The backlight module according to claim 16, wherein the second conductive layer comprises a plurality of conductive lines; and each of the conductive lines penetrates the dielectric layer to be connected to the signal lines.

18. The backlight module according to claim 16, wherein the dielectric layer is an insulating layer, and the second conductive layer completely covers the insulating layer.

19. The backlight module according to claim 6, wherein the transmission lines comprise at least one type of the transmission lines, and each column of the controllers is correspondingly connected to a same type of the transmission lines; and the backlight module further comprises a second conductive structure, and the transmission lines of the same type are electrically connected through the second conductive structure.

20. A display device, comprising a display panel and the backlight module, the backlight module comprising: a substrate; a metal layer disposed on the substrate, the metal layer comprising a plurality of signal lines and a plurality of first signal connection lines extending along a first direction, wherein the signal lines and the first signal connection lines are horizontally aligned with

each other on a same plane on a front side of the substrate and on a same plane on a back side of the substrate; and a plurality of light-emitting control structures disposed on the metal layer and arranged in a plurality of columns, wherein one of the signal lines is disposed on at least one side of each column of the light-emitting control structures, each of the light-emitting control structures in each column are connected to a corresponding one of the signal lines, and any two adjacent ones of the light-emitting control structures in each column of the light-emitting control structures are connected through one of the first signal connection lines, wherein each of the light-emitting control structures comprises a controller and at least one light-emitting unit, each of the controllers in each column of the light-emitting control structures and the corresponding signal line are electrically connected to the corresponding at least one light-emitting unit, all the controllers in each column of the light-emitting control structures are directly electrically connected to each other through a same-layer electrical connection path established by one of the first signal connection lines across each column of the light-emitting control structures, and the controllers are arranged on a same side in each column of the light-emitting control structures, wherein the display panel is disposed on the backlight module, wherein an orthographic projection of the signal lines does not overlap with an orthographic projection of the light-emitting control structures on the substrate.
