

# US Patent & Trademark Office

## Patent Public Search | Text View

---

|                      |                          |
|----------------------|--------------------------|
| United States Patent | 12401992                 |
| Kind Code            | B2                       |
| Date of Patent       | August 26, 2025          |
| Inventor(s)          | Kneckt; Jarkko L. et al. |

---

### Address randomization schemes

---

#### Abstract

Embodiments are disclosed for address changing schemes in a wireless communications system. Some embodiments include an access point (AP) that can establish two or more address profiles with a station (STA), establish a schedule for switching from a first address profile to a second address profile, where the first and second address profiles are of the two or more address profiles, and transmit a first data transmission using the first address profile. Some embodiments include switching from the first address profile to the second address profile based on the schedule, and transmitting a second data transmission using the second address profile. The schedule can be based on a randomized time synchronization function (TSF). The AP can establish a joint algorithm with the STA, and use the joint algorithm determine the first and the second address profiles as well as transition times for the schedule.

---

**Inventors:** Kneckt; Jarkko L. (Los Gatos, CA), Diwan; Aniruddha S. (San Jose, CA), Dominguez; Charles F. (San Carlos, CA), Dash; Debashis (San Jose, CA), Briggs; Elliot S. (Carmel, CA), Semersky; Matthew L. (San Jose, CA), Ginsburg; Noam (Haifa, IL), Thakur; Sidharth R. (San Jose, CA), Boodannavar; Veerendra (Cupertino, CA), Kasten; Welly (San Jose, CA), Kralian; Nathan A. (Danvers, MA), Borges; Daniel R. (San Francisco, CA), Shani; Oren (Saratoga, CA), Yong; Su Khiong (Palo Alto, CA), Yu; Yang (Redwood City, CA), Boger; Yoel (Shoham, IL), Liu; Yong (Campbell, CA)

**Applicant:** Apple Inc. (Cupertino, CA)

**Family ID:** 1000008778996

**Assignee:** Apple Inc. (Cupertino, CA)

**Appl. No.:** 17/896750

**Filed:** August 26, 2022

#### Prior Publication Data

|                     |                  |
|---------------------|------------------|
| Document Identifier | Publication Date |
|---------------------|------------------|

## Related U.S. Application Data

us-provisional-application US 63243682 20210913

---

## Publication Classification

**Int. Cl.:** H04W12/02 (20090101); H04W8/26 (20090101); H04W12/037 (20210101)

**U.S. Cl.:**

**CPC** H04W8/26 (20130101); H04W12/037 (20210101);

## Field of Classification Search

**CPC:** H04L (2101/622); H04L (61/5038); H04W (12/02); H04W (12/037); H04W (12/088); H04W (12/50); H04W (12/61); H04W (12/71); H04W (8/26); H04W (84/12)

---

## References Cited

### U.S. PATENT DOCUMENTS

| Patent No.   | Issued Date | Patentee Name | U.S. Cl. | CPC          |
|--------------|-------------|---------------|----------|--------------|
| 2009/0074187 | 12/2008     | Inoue et al.  | N/A      | N/A          |
| 2012/0213211 | 12/2011     | Remaker       | 370/338  | H04L 63/0421 |
| 2016/0128024 | 12/2015     | Frederiks     | 370/329  | H04W 72/04   |
| 2021/0014679 | 12/2020     | Liu           | N/A      | H04W 12/50   |
| 2023/0085657 | 12/2022     | Kneckt        | N/A      | H04W 12/02   |

### FOREIGN PATENT DOCUMENTS

| Patent No. | Application Date | Country | CPC |
|------------|------------------|---------|-----|
| 102084598  | 12/2010          | CN      | N/A |
| 111543111  | 12/2019          | CN      | N/A |
| 4002899    | 12/2021          | EP      | N/A |

### OTHER PUBLICATIONS

Extended European Search Report directed to related European Application No. 22194076.0, mailed on Jan. 26, 2023; 7 pages. cited by applicant  
Office Action for Chinese Application No. 202211119129.5, with machine translation attached, mailed May 20, 2025, 16 pages. cited by applicant

---

*Primary Examiner:* Tran; Phuc H

*Attorney, Agent or Firm:* Sterne, Kessler, Goldstein & Fox P.L.L.C.

---

## Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application claims benefit of U.S. Provisional Application No. 63/243,682, filed on Sep. 13, 2021, entitled, *Address Randomization Schemes*, which is incorporated herein by reference in its entirety.

## BACKGROUND

### Field

(1) The embodiments relate generally to improving privacy among wireless devices communicating in a wireless communication system.

### SUMMARY

(2) Some embodiments include an apparatus, method, and computer program product for address randomization schemes for devices in a wireless communications system such as a Wireless LAN (WLAN) system. An access point (AP) and a station (STA) can implement address randomization schemes that enable communications so that a bad actor cannot readily trace or detect device addresses. Some embodiments include an AP that can establish two or more address profiles with a STA, establish a schedule for switching from a first address profile to a second address profile, and transmit a first data transmission using the first address profile. The AP can switch from the first address profile to the second address profile based on the schedule, and transmit a second data transmission using the second address profile. The schedule for switching from the first address profile to the second address profile can be based on a randomized time synchronization function (TSF) parameter.

(3) The AP can establish new address profiles with the STA, as well as a first time when the new address profiles are available for use. The AP can also establish a second time when the AP begins operating on a different channel, and transmit on the different channel, a second data transmission using a third address profile of the new address profiles, after the first and second times. The AP can determine an end time for the new address profiles, where the third address profile is randomly selected from the new address profiles before the end time.

(4) In some embodiments, the AP can encrypt an aggregated media access control (MAC) Service Data Unit (A-MSDU), and after the encryption, create an over-the-air (OTA) packet number (PN.sub.OTA) that is different than a packet number (PN) corresponding to the A-MSDU, where the first data transmission includes the PN.sub.OTA, where the first address profile comprises an offset PN (PN.sub.Offset), and where the  $\text{PN.sub.OTA} = \text{PN} + \text{PN.sub.Offset}$ . Further, after the encryption, the AP can create an OTA sequence number (SN.sub.OTA) that is different than a sequence number (SN) corresponding to the A-MSDU, where the first data transmission includes the SN.sub.OTA, where the first address profile includes an offset SN (SN.sub.Offset), and where the  $\text{SN.sub.OTA} = \text{SN} + \text{SN.sub.Offset}$ .

(5) After the encryption, the AP can apply an AP identifier of the first address profile, where the first data transmission includes the first AP identifier that is transmitted OTA.

(6) To establish the two or more address profiles, the AP can establish a joint algorithm with the STA, and use the joint algorithm determine the first and the second address profiles as well as transition times for the schedule. To establish the joint algorithm, the AP can receive an individual address set algorithm, a MAC address seed, and a proposed address set average duration from the STA. In response, the AP can transmit an individual address set start time seed, an individual address set end time seed, a group address algorithm, and an AP MAC address seed.

(7) In some embodiments, the AP can receive from the STA a notification of a colliding MAC address, where the notification includes: the colliding MAC address, a proposed new MAC address for the STA, a time when the proposed new MAC address for the STA is in use, or a proposed new MAC address for the AP. The AP can transmit to the STA a confirmation message corresponding to the notification.

(8) In some embodiments, a STA can establish two or more address profiles with an AP, establish a schedule for switching from a first address profile to a second address profile, and receive a first

data transmission comprising a first receiving address (RA) corresponding to the first address profile. The STA can transmit a block acknowledgement (BA) corresponding to the first data transmission received. The STA can switch from the first address profile to the second address profile based on the schedule, and receive a second data transmission including a second RA corresponding to the second address profile, where the first RA and the second RA are different. The STA can establish new address profiles with the AP as well as a first time when the new address profiles are available for use. The STA can establish a second time when the AP begins operating on a different channel, and after the first and second times, transmit on the different channel a second data transmission using a third address profile of the new address profiles. The STA can determine an end time for the new address profiles, where the third address profile is randomly selected from the new address profiles before the end time.

(9) In some embodiments, the STA can determine a packet number (PN) using an over-the-air (OTA) packet number (PN.sub.OTA) of the first data transmission and an offset PN (PN.sub.offset) of the first address profile, and determine a sequence number (SN) using an (OTA) sequence number (SN.sub.OTA) of the first data transmission and an offset SN (SN.sub.Offset) of the first address profile, where the PN and the SN correspond to an encrypted aggregated MAC Service Data Unit (A-MSDU) of the first data transmission. The determinations can be based on the equations as follows:  $PN = PN.sub.OTA - PN.sub.Offset$ , and  $SN = SN.sub.OTA - SN.sub.Offset$ . The STA can order frames of the first data transmission according to the SN, and decrypt the encrypted A-MSDU. In some embodiments, the STA can establish a joint algorithm with the AP, wherein the joint algorithm is used to establish the first and the second address profiles as well as transition times for the schedule.

---

## Description

### BRIEF DESCRIPTION OF THE FIGURES

(1) The accompanying drawings, which are incorporated herein and form part of the specification, illustrate the presented disclosure and, together with the description, further serve to explain the principles of the disclosure and enable a person of skill in the relevant art(s) to make and use the disclosure.

(2) FIG. 1 illustrates an example system for address randomization schemes, in accordance with some embodiments of the disclosure.

(3) FIG. 2 illustrates a block diagram of an example wireless system supporting address randomization schemes, according to some embodiments of the disclosure.

(4) FIG. 3A illustrates an example of a hidden access point (AP) system.

(5) FIG. 3B illustrates an example of a hidden AP operation.

(6) FIG. 4A illustrates an example of a system with randomized individual address sets, according to some embodiments of the disclosure.

(7) FIG. 4B illustrates an example of scheduling randomized individual address sets, according to some embodiments of the disclosure.

(8) FIG. 5A illustrates an example of a system with randomized group address sets, according to some embodiments of the disclosure.

(9) FIG. 5B illustrates an example of scheduling randomized group address sets including channel switching, according to some embodiments of the disclosure.

(10) FIG. 6 illustrates an example method for receiving a physical layer protocol data unit (PPDU) that includes a randomized individual address set, according to some embodiments of the disclosure.

(11) FIG. 7 illustrates an example of group address set randomizing timing synchronization function (TSF), according to some embodiments of the disclosure.

- (12) FIG. 8 illustrates an example of signaling for configuring randomized address sets, according to some embodiments of the disclosure.
- (13) FIG. 9 illustrates an example of signaling for updating randomized address sets, according to some embodiments of the disclosure.
- (14) FIG. 10 illustrates an example of signaling for configuring joint algorithms that determine randomized address sets, according to some embodiments of the disclosure.
- (15) FIG. 11 illustrates an example of signaling for Media Access Control (MAC) address collision detection and avoidance, according to some embodiments of the disclosure.
- (16) FIG. 12 illustrates an example method for data transmission with randomized address sets, according to some embodiments of the disclosure.
- (17) FIG. 13A illustrates a diagram showing data that is delivered to Galois/counter mode (GCM) encryption.
- (18) FIG. 13B illustrates an example of an encryption block diagram supporting randomized address sets, according to some embodiments of the disclosure.
- (19) FIG. 14A illustrates an example of an expanded Galois/counter mode (GCM) protocol (GCMP) MAC Protocol Data Unit (MPDU).
- (20) FIG. 14B illustrates an example of additional authentication data (AAD) for protocol version 0 (PV0) MPDU.
- (21) FIG. 15 illustrates an example privacy enhanced (PE) multi-link device (MLD) system supporting address randomization schemes, according to some embodiments of the disclosure.
- (22) FIG. 16 illustrates an example PE MLD system including address and identifier randomization, according to some embodiments of the disclosure.
- (23) FIG. 17 illustrates an example of multiple MLD address types for address randomization, according to some embodiments of the disclosure.
- (24) FIG. 18A illustrates an example of a data transmission supporting PE MLD randomized address, according to some embodiments of the disclosure.
- (25) FIG. 18B illustrates an example MPDU of a portion of an Aggregate MPDU (A-MPDU) subframe including an encrypted MLD address, according to some embodiments of the disclosure.
- (26) FIG. 18C illustrates a basic A-MAC Service Data Unit (A-MSDU) subframe structure.
- (27) FIG. 19 illustrates an example of changing an over-the-air (OTA) MLD MAC address for group addressed PPDU, according to some embodiments of the disclosure.
- (28) FIG. 20 illustrates an example of signaling for configuring joint algorithms that determine address sets for MLDs and signaling for address collision notification, according to some embodiments of the disclosure.
- (29) FIG. 21 illustrates an example method for data transmission between PE MLDs, according to some embodiments of the disclosure.
- (30) FIG. 22A illustrates a diagram showing data that is delivered to Galois/counter mode (GCM) decryption.
- (31) FIG. 22B illustrates an example of a decryption block diagram supporting randomized address sets, according to some embodiments of the disclosure.
- (32) FIG. 23 is an example computer system for implementing some embodiments or portion(s) thereof.
- (33) The presented disclosure is described with reference to the accompanying drawings. In the drawings, generally, like reference numbers indicate identical or functionally similar elements. Additionally, generally, the left-most digit(s) of a reference number identifies the drawing in which the reference number first appears.

#### DETAILED DESCRIPTION

(34) Some embodiments include address randomization schemes for devices including multi-link devices (MLDs) in a wireless communications system that prevent a bad actor from tracing, tracking, and/or detecting Media Access Control (MAC) addresses of access points (APs), stations

(STAs), privacy enhanced (PE) AP MLDs, and PE non-AP MLDs. Since the MAC addresses are not readily traceable and/or trackable, security of the wireless communications among the devices is improved.

(35) FIG. 3A illustrates example **300** of a hidden AP system that can include APs in vehicles or mobile APs. Example **300** includes hidden AP **305**, STA1 **315** and STA2 **325**. When hidden AP **305** begins to operate, AP **305** can randomize parameters that are static for the short duration of operation. For example, AP **305** can transmit a group transmission **335a** and **335b** to STA1 **315** and STA2 **325** or an individual transmission **345** to STA2 **325**. For the short duration of operation, MAC addresses X, Y, and Z are used until the short duration of operation ends. When AP **305** begins to operate again, different randomized parameters are used and different values of MAC addresses X, Y, and Z are used that remain static for the short duration of operation. By using randomized parameters for a short duration of operation, the devices using the changed MAC addresses can be difficult to determine.

(36) FIG. 3B illustrates example **350** of a hidden AP operation. Example **350** includes 3 short duration operations. At the start of the first operation **360**, AP1 can randomize MAC addresses and parameters that are used for the duration of operation that ends at **365**. At the start of the second operation **370**, AP2, essentially a different AP, randomizes MAC addresses and parameters and begins operating until the duration ends at **375**. At the start of the third operation **380**, AP3, yet a different AP, randomizes MAC addresses and parameters and begins operating until the duration ends at **385**. While the randomized addresses and parameters provide a measure of security, the hidden AP approach is not practical in the operation of wireless communication systems that have a longer duration of operation, including but not limited to Wi-Fi as described in IEEE P802.11REVme\_D0.0, Draft Standard for Information technology—Telecommunications and information exchange between systems Local and metropolitan area networks—Specific requirements, Part 11: Wireless LAN Medium Access Control (MAC) and Physical Layer (PHY) Specifications “IEEE P802.11REVme”.

(37) FIG. 1 illustrates example system **100** for address randomization schemes, in accordance with some embodiments of the disclosure. System **100** includes privacy enhanced (PE) AP multi-link device (MLD) **110** that provides PE non-AP MLD **120** and STA **130** with access to network **150**. System **100** also includes AP **160** (e.g., a single link device) that provides STA **180** and STA **170** (e.g., a single link device) with access to network **150**. PE AP MLD **110** can include affiliated PE APs (e.g., PE AP **110a-110c**) and PE non-AP MLD **120** can include affiliated PE non-AP STAs (e.g., PE non-AP STAs **120a-120c**) that communicate via multiple links: link **1 105**, link **2 107**, and link **3 109**. PE non-AP MLD **120**, STA **130**, STA **180**, and STA **170** can be electronic devices that may include but are not limited to a cellular phone, a smart phone, a tablet, a personal digital assistant (PDA), or a laptop. Network **150** may include but is not limited to, any of or any combination of local area networks (LANs), metropolitan area networks (MANs), wireless local area networks (WLANs), and/or the Internet. Non-AP MLD **120** and STA **130** in proximity to AP MLD **110** may associate with AP MLD **110**. STA **180** and STA **170** in proximity to AP **160** may associate with AP **160**.

(38) In some embodiments, AP **160** can establish multiple address profiles with STA **180** and multiple different address profiles with STA **170**, establish a schedule for switching from one address profile to another, and transmit data using the address profiles that are currently in use. In some embodiments, MLD devices can include two types of address randomization schemes: one at the MLD address level and another at link-specific address level. PE AP MLD **110** and PE non-AP MLD **120** can randomize MLD addresses and MLD level parameters so that MLD addresses and MLD level parameters are not transmitted unencrypted over the air. The randomized MLD addresses and MLD level parameters can be different for each link (e.g., link **1 105**, link **2 107**, and link **3 109**) used by PE AP MLD **110** and PE non-AP MLD **120**. In addition, an affiliated PE AP (e.g., PE AP **110a**) of PE AP MLD **110** can establish multiple address profiles that are link-specific

with STA 130 and multiple address profiles with an affiliated PE non-AP STA (e.g., PE non-AP STA 120a) of PE non-AP MLD 120, establish a schedule for switching from one address profile to another, and transmit data using the address profiles that are currently in use.

(39) FIG. 2 illustrates a block diagram of an example wireless system supporting address randomization schemes, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. 2 may be described with reference to elements from FIG. 1. For example, system 200 may be any of the electronic devices (e.g., AP 160, PE AP MLD 110, PE AP 110a-110c, PE non-AP MLD 120, PE non-AP STAs 120-120c, STAs 130, STA 180, and STA 170) of system 100. System 200 includes one or more processors 265, transceiver(s) 270, communication interface 275, communication infrastructure 280, memory 285, and antenna 290. Memory 285 may include random access memory (RAM) and/or cache, and may include control logic (e.g., computer instructions) and/or data. One or more processors 265 can execute the instructions stored in memory 285 to perform operations enabling wireless system 200 to transmit and receive wireless communications, including the functions for performing address randomization schemes herein. In some embodiments, one or more processors 265 can be “hard coded” to perform the functions herein. Transceiver(s) 270 transmits and receives wireless communications signals including wireless communications supporting address randomization schemes according to some embodiments, and may be coupled to one or more antennas 290 (e.g., 290a, 290b). In some embodiments, a transceiver 270a (not shown) may be coupled to antenna 290a and different transceiver 270b (not shown) can be coupled to antenna 290b. Communication interface 275 allows system 200 to communicate with other devices that may be wired and/or wireless. Communication infrastructure 280 may be a bus. Antenna 290 may include one or more antennas that may be the same or different types.

(40) To increase privacy and security of wireless communications and traceability of MAC addresses, some embodiments include individual (also referred to herein as unicast) address sets and group (also referred to herein as groupcast) address sets that include addresses and parameters that always change, but at different (e.g., random) times. Having the many changes avoids significant one-time changes that may be traceable. Individual address set data used in transmissions to/from an AP (e.g., AP 160) and an associated STA (e.g., STA 180 or STA 170) should be known only by the AP and the associated STA (e.g., between AP 160 and STA 180, and between AP 160 and STA 170). Individual address set changes and availability are scheduled only between the AP and the associated STA. Group address sets used by an AP (e.g., AP 160) should be known by all associated STAs (e.g., STA 180 and STA 170). An AP (e.g., AP 160) may schedule the group address set in use for all associated STAs (e.g., STA 180 and STA 170). Individual addresses in individual address sets and group addresses in group address sets in use are scheduled and can change based on randomized time synchronization function (TSF) parameter values (e.g., times.)

(41) Looking at an MLD example, link-specific individual addresses used in transmissions on link 1 105 to/from a PE AP (e.g., PE AP 110a) and an associated STA (e.g., STA 130 or PE non-AP STA 120a) should be known only by the AP and the associated STA. Individual address changes and availability are scheduled only between the AP and the associated STA. In the MLD example, group addresses used by PE AP (e.g., PE AP 110a) should be known by all associated STAs (e.g., STA 130 and PE non-AP STA 120a). APE AP (e.g., PE AP 110a) may schedule the group address in use for all associated STAs (e.g., STA 130 and PE non-AP STA 120a). Individual addresses and group addresses in use are scheduled and can change based on randomized MLD-level time synchronization function (TSF) parameter values (e.g., times).

(42) FIG. 4A illustrates example system 400 with randomized individual address sets, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. 4A may be described with reference to elements from FIG. 1. For example, AP 410 can be AP 160 or one of PE AP 110a-110c, and associated STA 420 can be STA 130, STA 180, STA 170, or one of PE non-AP STA 120a-120c of FIG. 1.

- (43) AP **410** includes individual address set profiles **418**. In system **400**, 6 individual address set profiles (herein also known as individual address profiles) are shown: individual address profiles **411-416**. Associated STA **420** includes individual address set profiles **430** that includes 6 individual address profiles **431-436** that correspond respectively to the individual address profiles **411-416** of AP **410**.
- (44) An individual address set profile is shown below in Table 1. Individual Address Set.
- (45) TABLE-US-00001 TABLE 1 Individual Address Set Addresses and Identifier Type Parameters  
AP/BSS identifier BSSID.sub.unicast Color Field value STA identifier STA Link  
Address.sub.unicast STA AID Encryption parameters PN Offset.sub.unicast Reception parameters  
SN Offset (TID).sub.unicast
- (46) An individual address set (e.g., one of **411-416**) defines the addresses and identifiers for the individually addressed transmissions between AP **410** and associated STA **420**. In some embodiments, the addresses and identifiers are only known by AP **410** and associated STA **420** to provide address privacy. In system **400**, AP **410** and associated STA **420** established 6 individual address sets **411-416**, for communications. In some embodiments (not shown), AP **410** can configure different individual address set profiles (e.g., **411-416**) with different associated STAs (e.g., STA **420** may include individual address sets **411-414**, while a different STA (not shown) may be configured with individual address sets **415-416**).
- (47) Some embodiments include features and operations for address randomization as shown in Table 2. Rules for APs and STAs that use Address Randomization.
- (48) TABLE-US-00002 TABLE 2 Rules for APs and STAs that use Address Randomization  
Recommendations to Improve Privacy Description Use Protected management (802.11w)  
Associated STAs only send encrypted management frames frames Use only secure security Wi-Fi  
Protected Access v3 Personal Mode (WPA3 Personal) mode Do not use unsecure security open  
network, WEP, WPA, WPA2, TRIP cipher suites modes, like: Implement privacy client Wi-Fi  
Client Privacy (WPA3 Release 3, 802.11aq): privacy mechanisms: Randomized MAC Addresses,  
DHCP Pool Exhaustion (reclaim IP addresses from deleted users, if they run out), DHCP Lease  
Timeout <2 hours The network should use The Preassociation Security Negotiation (PASN)  
protocol preassociation security should be used to protect non-associated STAs frames transmitted  
to AP Use protected Block Acks The Block Ack Request frames should be protected, so that no  
device can change the SN from which the receiver keeps reorder buffer Use Beacon protection The  
Beacon frames should contain integrity check sum, so that receivers can verify the integrity of the  
received Beacon frames Use encrypted A-MSDU to The transmitted data frames are A-MSDU  
aggregated and both protect SA and DA the A-MSDU and the data payload are encrypted
- (49) The mechanisms described below in Table 3. Recommendations to Improve Privacy help to keep AP **410** and associated STA **420** more private and prevent ways to trace associated STA **420** and AP **410**.
- (50) TABLE-US-00003 TABLE 3 Recommendations to Improve Privacy Recommendations to Improve Privacy Description The following operations are The changing MAC Addresses deny the use of the following disallowed: features: MAC Address Filtering or Access Control, MAC Address Identification, MAC Address Memory (MAC addresses will change and can identify a STA only temporarily) To protect privacy Each random MAC address has: Randomize AP address The Locally Administered bit, which shall be set to “1”, and The Unicast/Multicast bit, which shall be set to “0”  custom character - the other 46 bits are set to random values AP hides its SSID and it is not transmitted in Beacons, etc. (e.g., frames) AP randomized the initial values of Time Stamp field (TSF), Sequence numbers of the PPDUs, Dialog token values to identify management frames, scrambler seeds in PHY preambles, 802.11aq scanning privacy is implemented for AP and STA, AP should scan at random times so that other STAs cannot detect AP to be scanning The element values that AP sends should not contain identifiers that can be used to fingerprint the AP, i.e. the elements should not contain serial numbers of other information that is STA specific. The order of

the proprietary elements and elements should be random unless the order is defined in the standard. The random order is applied in all frames, including authentication, GAS, association, etc

(51) In some embodiments, the AP/basic service set (BSS) identifier and corresponding BSSID.sub.unicast and color field value, are known by all associated STAs, but the remaining information in Table 1. Individual Address configured between associated STA **420** and AP **410** are known only by associated STA **420** and AP **410**. When the AP/BSS identifier is known by all the associated STAs an associated STA can detect if an associated AP is transmitting or receiving data which may prevent collisions. STAs may use spatial reuse and have more simultaneous transmissions. This embodiment may be useful, when AP **410** has only few associated STAs or when AP **410** and STA **420** are located far apart.

(52) In some embodiments, individual addresses used in transmissions to/from an AP **410** and associated STA **420** should be known only by AP **410** and associated STA **420**. Individual address changes and availability are scheduled only between AP **410** and associated STA **420**.

(53) FIG. **4B** illustrates example **450** of scheduling randomized individual address sets, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **4B** may be described with reference to elements from FIG. **4A**. In example **450**, AP **410** and associated STA **420** may configure and establish the individual address sets **411-416** (and corresponding individual address sets **431-436**) to change at random times known only by AP **410** and STA **420**. Example **450** illustrates the configuration and usage of the various individual address sets on on a timeline on link X, where link X can correspond in the MLD case to link **1 105**, link **2 107**, or link **3 109**.

(54) At **460**, multiple address sets may be negotiated. For example, associated STA **420** and AP **410** configure and establish **3** address sets: individual address set **411 (431)**, **412 (432)**, and **413 (433)** to be used between time **460** and time **480**.

(55) After the configuration and up to time **465**, individual address set **411 (431)** can be used to communicate between AP **410** and STA **420** (e.g., uplink and/or downlink communications).

(56) Between time **465** and time **470**, individual address set **412 (432)** can be used to communicate between AP **410** and STA **420**.

(57) Between time **470** and time **480**, individual address set **413 (433)** can be used to communicate between AP **410** and STA **420**.

(58) At **480**, new individual address sets (e.g., individual address sets **413 (433)**, **414 (434)**, and **415 (435)**) can be configured. In some embodiments, one or more individual address sets can be in use at a time. For example, between **480** and **485**, associated STA **420** and AP **410** may randomly select one of individual address sets **413 (433)**, **414 (434)**, and **415 (435)** for frame transmission. Having multiple individual address profiles available at the same time to AP **410** and associated STA **420** for communications is different than the hidden AP example **350** of FIG. **3B**, where only one static individual address set is available for the short duration operation.

(59) At **485**, new individual address sets (e.g., individual address sets **415 (435)** and **416 (436)**) can be configured. After **485**, associated STA **420** and AP **410** may randomly select one of individual address sets **415 (435)** and **416 (436)** for frame transmission.

(60) FIG. **6** illustrates example method **600** for receiving a physical layer protocol data unit (PPDU) that includes a randomized individual address set, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **600** may be described with reference to elements from other figures in the disclosure. For example, method **600** can be performed by associated STA **420** of FIG. **4A** in communication with AP **410** of FIG. **4A**. In method **600**, the individual address set profiles including the APBSS identifier, are known only by AP **410** and associated STA **420**. In otherwords, associated STA **420** does not know the AP/BSS identifier (and corresponding addresses and parameters) in other individual address sets (e.g., Set **7** of another associated STA that is not shown.) In some embodiments, a color field value may be configured for an AP/BSS identifier, or a color field value may be set to a random value between 0-

63. In some examples, AP **410** transmits a downlink frame to a STA (e.g., STAs **130**, **170**, **180**) using one color value. In some examples, AP **410** may use legacy physical layer protocol data unit (PPDU) formats in transmissions to legacy STAs. As shown below in method **600**, STA **420** receives at least one MAC header from a PPDU.

(61) At **605**, STA **420** receives a preamble and detects a PPDU duration.

(62) At **610**, STA **420** receives a MAC header and proceeds to **615**, applying reception rules.

(63) At **615**, STA **420** determines whether a payload is received. If a payload is not received, method **600** proceeds to **620**. Otherwise, method **600** proceeds to **625**.

(64) At **620**, when a payload is not received, STA **420** can set the channel as being Busy for a duration of the PPDU.

(65) At **625**, STA **420** determines whether a BSSID is within co-hosted BSSs or multiple BSSIDs. When the BSSID is not within co-hosted BSSs or multiple BSSIDs (e.g., the BSSID detected does not match the BSSID corresponding to the individual address set being used), method **600** proceeds to **630**. Otherwise, method **600** proceeds to **635**.

(66) At **630**, STA **420** sets a regular network allocation vector (NAV) (e.g., the transmission was not initiated by STA **420**.)

(67) At **635**, STA **420** determines whether the receiving address (RA) is equal to the MAC address of STA **420** (e.g., STA link Address.sub.unicast of the individual address set being used). When the RA is equal to the MAC address of STA **420**, method **600** proceeds to **645**. Otherwise, method **600** proceeds to **640**.

(68) At **645**, STA **420** receives the payload of the PPDU detected.

(69) Returning to **640**, when the RA is not equal to the MAC address of STA **420**, STA **420** may stop the reception and go into an intra-PPDU power save mode.

(70) FIG. 5A illustrates an example system **500** with randomized group address sets, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. 5A may be described with reference to elements from FIG. 1. For example, AP **510** can be AP **160** or one of PE AP **110a-110c**, and associated STAs **520a**, **520b** can be STA **130**, STA **180**, STA **170**, or one of PE non-AP STA **120a-120c** of FIG. 1.

(71) AP **510** defines group address set parameters and the number of configured address sets **511-516**. All group address sets are configured to all associated STAs **520a**, **520b**. AP **510** includes group address set profiles **518**. In system **500**, **6** group address sets (herein also known as group address profiles) are shown: group address profiles **511-516**. Associated STAs **520a**, **520b** include group address set profiles **518a**, **518b** that includes corresponding group address profiles **511a-516a**, **511b-516b** that correspond respectively to the group address profile **511-516** of AP **510**. In some embodiments group address set profiles **511-516** are substantially the same as group address profiles **511a-516a**, **511b-516b**.

(72) A group address set profile is shown below in Table 4. Group Address Set.

(73) TABLE-US-00004 TABLE 4 Group Address Set Addresses and Identifier Type Parameters AP identification BSSID.sub.group Group AID Reception parameters SN Offset group Encryption parameters PN Offset group BSS parameters TSF.sub.Offset Change Sequence Counters

(74) The group address set profile is used to transmit group data frames, group control frames, and group management frames to all associated STAs **520a**, **520b**. The group address sets are known by all associated STAs **520a**, **520b**. Associated STAs **520a**, **520b** can receive the group frames and associated STAs **520a**, **520b** know what BSS specific parameter values they may expect. The group address set configures coming BSS parameters changes including but not limited to TSF offset, Change Sequence Number, etc.

(75) FIG. 5B illustrates example **550** of scheduling randomized group address sets including channel switching, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. 5B may be described with reference to elements from FIG. 5A. In example **550**, AP **510** and associated STAs **520a**, **520b** may configure and establish the group address sets

**511-516** (and corresponding individual address sets **531a-536a**, **531b-536b**) to change at random times. (Even though example **550** appears to be periodic, the time between changes e.g., between **565**, **570**, and **575**, can vary.) Example **550** illustrates the configuration and usage of the various individual address sets on a timeline on link X, where link X can correspond in the MLD case to link **1 105**, link **2 107**, or link **3 109**. In example **550**, one group address set is in use at a time.

(76) At **555**, multiple address sets may be negotiated. For example, AP **510**, associated STA **520a**, and associated STA **520b** configure and establish **3** address sets: group address set **511** (**511a**, **511b**), **512** (**512a**, **512b**), and **513** (**513a**, **513b**) to be used at different times between time **555** and time **570**.

(77) After the configuration and up to time **560**, group address set **511** (**511a**, **511b**), can be used to communicate from AP **510** to STAs **520a**, **520b**.

(78) Between time **560** and time **565**, group address set **512** (**512a**, **512b**), can be used to communicate from AP **510** to STAs **520a**, **520b**.

(79) Between time **565** and time **570**, group address set **513** (**513a**, **513b**), can be used to communicate from AP **510** to STAs **520a**, **520b**.

(80) At **570**, new group address sets are configured for operation during certain times. For example, group address sets **513** (**513a**, **513b**) are in use between time **570** and time **575**, group address sets **514** (**514a**, **514b**) are in use between time **575** and time **580**, and **515** (**515a**, **515b**) are in use after time **580**.

(81) In some embodiments, AP **510** can also establish with STA **520**, a time (e.g., **575**) when the AP **510** begins operating on a different channel noted at **590**. Thus, in addition to changing at time **575** to use group address sets **514** (**514a**, **514b**), AP **510** begins operating on a different channel. Accordingly, STAs **520a** and **520b** tune to the different channel at substantially time **575** to receive group address communications according to group address sets **514** (**514a**, **514b**) on the different channel. Further reception may remain on the different channel until AP **510** updates the schedule and/or the operating channel.

(82) FIG. 7 illustrates example **700** of group address set randomizing timing synchronization function (TSF), according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. 7 may be described with reference to elements from other figures in the disclosure. For example, example **700** can be performed by AP **520** of FIG. 5A.

(83) In some embodiments, when TSF=0, AP **510** transmits a Delivery Traffic Indication Message (DTIM) beacon frame at **710a**. After a DTIM beacon AP **510** sends buffered group addressed frames. AP **510** transmits a Traffic Indication Message (TIM) Beacon frame at **710b** and **710c**. Beacon frames can have a fixed transmission interval (e.g., 100 ms) and Target Beacon Transmission Time (TBTT) occurs on TSF times that are multiples of the Beacon interval. As described above, Table 4. Group Address Set can include BSS parameters that are randomized including a TSF offset. In other words, the group address set may change and the TSF time may change at **720**. When the TSF time is changed, the Beacon frame transmission time can change correspondingly to **730a**. In some embodiments, the Beacon frame is transmitted when TSF(Mod Beacon transmission interval)=0. Power saving STAs need to be aware of the AP group address sets and their individual address sets so that STAs may receive a Beacon frame.

(84) In some examples, every X:th (X=4) beacon a DTIM beacon is transmitted. The DTIM interval may be changed in the group parameters randomization. After time the group address set and TSF change at **720**, the following DTIM beacon occurs at **730b** followed by TIM beacon **730c**. In some embodiments, a new group address set may be signaled every Yth DTIM beacon (e.g., every 3.sup.rd DTIM beacon). STAs may utilize unicast request/response signaling to fetch the group address sets. Buffered group data frames transmitted after a DTIM beacon should use the same group address set.

(85) FIG. 8 illustrates example **800** of signaling for configuring randomized address sets, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. 8 may

be described with reference to elements other figures in the disclosure. For example, AP **810** can be AP **160** or one of PE AP **110a-110c** of FIG. **1**, and STA **820** can be STA **130**, STA **180**, STA **170**, or one of PE non-AP STA **120a-120c** of FIG. **1**. Group address sets and individual address sets may operate in different schedules, and they may be configured into use during an association as shown in example **800**. The association may configure the exact parameters of the individual and groupcast address sets. This mechanism may include update frames to update new individual and/or group address sets before the old ones expire. The association signals configure the unicast and groupcast address sets. The first unicast address set may be taken into use immediately after association.

(86) At **830**, AP **810** may transmit a Beacon frame that may signal support for address randomization and minimum number of individual address sets in association. The Beacon frame can include robust security network (RSN) element (RSNE) that includes an indication of: Preassociation Security Negotiation (PASN) protocol, fast basic service set (BSS) transition (FT), authentication and key management (AKM), Robust Security Network Extension element (RSNEXE), Mobility Domain element (MDE), and/or Address Randomization supported.

(87) At **840**, authentication occurs between STA **820** and AP **810**. The authentication may include PASN encryption setup, or the PASN encryption may be configured between STA **820** and AP **810** before the authentication. The authentication request includes the STA **820** association and authentication MAC address. The authentication response includes the AP **810** association and authentication MAC address.

(88) At **850**, STA **820** transmits a PASN protected Association Request that proposes one or more individual address sets and other association parameters. An individual address set can include: a STA MAC address, uplink (UL) sequence number (SN) offsets (e.g., separate SN offset for the traffic identifier (TID) specific SNs), UL packet number (PN) offset, proposed start time and end time of the individual address set. The other association parameters can include PHY and MAC capabilities of the STA.

(89) The Association Request frame may also contain the MAC-SAP MAC address of STA **820** that STA **820** uses in frame encryption and the frame may include the MAC address STA **820** uses for authentication and association. Similarly, the Association Response may contain the MAC-SAP MAC address of AP **810** that AP **810** uses in frames encryption and the frame may include the MAC address AP **810** uses for authentication and association.

(90) At **860**, AP **810** can transmit a PASN protected Association Response that includes an indication of success (or not), one or more individual address sets, one or more group address sets, and other association parameters. For example, an individual address set can include: a corresponding AP MAC address (e.g., BSSID.sub.unicast, association ID (AID) value, color field value, downlink (DL) SN offsets (e.g., SN offset for STA specific and TID specific SNs), DL individual PN offset, and a schedule for an individual address set.

(91) AP **810** configures groupcast address sets, defines all parameters and schedules in association response. For example, the Association Response can include a group address set that includes: AP MAC address, DL SN offset, DL group PN Offset, TSF Offset, Change Sequence Counter value, and/or a group address set start and end time. After groupcast address set setup, the STA may receive group frames.

(92) FIG. **9** illustrates example **900** of signaling for updating randomized address sets, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **9** may be described with reference to elements other figures in the disclosure. For example, AP **910** can be AP **160** or one of PE AP **110a-110c** of FIG. **1**, and STA **920** can be STA **130**, STA **180**, STA **170**, or one of PE non-AP STA **120a-120c** of FIG. **1**.

(93) The individual and/or group address sets may be updated with new signaling messages. The same signaling may configure multiple individual (e.g., unicast) and group (e.g., groupcast) address sets. The address sets should be updated before the existing address sets expire. AP **910** or STA **920**

may initiate an address set update. AP **910** may send an unsolicited Address Set Response frame to provide group address set parameters and AP **910** parameters for individual address sets.

(94) In some embodiments, AP **910** and STA **920** may setup a recovery individual address set. The recovery address set is used only if all unicast address sets have expired (e.g., STA **920** may operate in a long term power save and not receive an address set update.) After a transmission with the recovery address set, AP **910** or STA **920** should update their address sets and recovery address set. In some embodiments, simple devices including IoT-devices may have only the recovery address set in use (e.g., the recovery address set is used to transmit the next burst of frames.)

(95) Example **900** illustrates signaling for updating the randomized address sets.

(96) At **930**, STA **920** is associated with AP **910** and updates individual and groupcast address sets.

(97) At **940**, STA **920** can transmit a Robust MGMT frame that includes an Address Set Update Request that includes one or more individual address sets. The corresponding parameters of an updated individual address set can include: STA **920** MAC address, UL SN Offset (e.g., SN offset for TID specific SNs), UL individual PN offset, and/or proposed start individual address set time and end time.

(98) At **950**, AP **910** can transmit a Robust MGMT frame that includes an Address Set Update Response that includes one or more individual address sets, and/or one or more group address sets. An updated individual address set can include: AP **910** MAC address, AID, color field value, DL SN offset (e.g., SN offset for STA specific and TID specific SNs), individual PN offset, and/or corresponding individual address set start and end times. The updated group address set can include: AP **910** MAC address, DL group SN offset, DL group PN offset, TFS offset, change sequence counter value, and/or group address set start and end times.

(99) FIG. **10** illustrates example **1000** of signaling for configuring joint algorithms that determine randomized address sets, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **10** may be described with reference to elements of other figures in the disclosure. For example, AP **1010** can be AP **160** or one of PE AP **110a-110c** of FIG. **1**, and STA **1020** can be STA **130**, STA **180**, STA **170**, or one of PE non-AP STA **120a-120c** of FIG. **1**.

(100) The association may configure joint algorithms to update the address set parameters during the association. In association signaling, AP **1010** and STA **1020** can agree on a set of joint algorithms to calculate individual address sets and group address sets. The algorithms may also configure address set transition times and the number of address sets in use. The associated AP (e.g., AP **1010**) may change the algorithms or the parameter values used for address sets. For example, if a STA has disassociated from a BSS, a change of the groupcast address set algorithm ensures that only associated STAs (e.g., STA **1020**) can know the next address of the AP. Alternatively, AP **1010** can maintain the algorithms for group address sets, so that STAs that reassociate with AP **1010** may calculate the current AP parameters and discover AP **1010**.

(101) The Association Request frame may also contain the MAC-SAP MAC Address of the STA **1020** that STA **1020** uses in frames encryption and the frame may include the MAC address STA **1020** uses for authentication and association. Similarly, the Association Response may contain the MAC-SAP MAC Address of AP **1010** that AP **1010** uses in frame encryption and the frame may include the MAC address AP **1010** uses for authentication and association.

(102) At **1030**, AP **1010** may transmit a Beacon frame that may signal support for address randomization and minimum number of individual address sets in association. The Beacon frame can include RSNE that includes an indication of: PASN protocol, FT, AKM, RSNXE, MDE, and/or Address Randomization supported.

(103) At **1040**, authentication occurs between STA **1020** and AP **1010**.

(104) At **1050**, STA **1020** transmits a PASN protected Association Request that proposes an individual address set algorithm including: algorithm parameters, a random value, and MAC address seed. The Association Request can also include an average duration for individual address sets, and other association parameters (e.g., PHY & MAC capabilities).

(105) At **1060**, AP **1010** can transmit a PASN protected Association Response that includes an indication of success (or not), an individual address algorithm and includes: algorithm parameters, a random value, a first AP MAC address seed, and/or individual address set start and end time seeds. The Association Response can also include a group address algorithm and include a random value and/or a second AP MAC address seed, where the first AP MAC address seed are different. In other words, group addressed transmissions and individual transmissions may be selected independently. For example, MAC Address used for group address transmission cannot be calculated by monitoring the individual addresses. The Association Response can include other association parameters (e.g., PHY & MAC capabilities.)

(106) At **1070**, STA **1020** has associated with AP **1010** and has configured individual address sets and/or group address sets as described in Table 1. Individual Address and/or Table 4. Group Address Set. STA **1020** and AP **1010** also have a schedule for changing individual address sets and group address sets.

(107) AP **1010** and STA **1020** use the same algorithms and parameters to calculate the same updated parameters values. In other words, a STA have certain parameter values and a corresponding algorithm for the individual address set. One group address set may be available at a time. The algorithm may use values that are stored by other means, including but not limited to: MAC address seed, Link Id, authentication MAC address, TSF, AID, etc. The joint algorithm ensures that there is no need to signal updates new random address set values to AP **1010** and STA **1020**. Accordingly, STA **1020** and AP **1010** power saving are improved and the management traffic overhead is reduced. Further, as the address change is more robust, there is no need to re-authenticate or re-associate, due to lost AP addresses. In some embodiments, the joint algorithm may consume less memory, than storing incoming new parameters.

(108) FIG. **11** illustrates example **1100** of signaling for MAC address collision detection and avoidance, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **11** may be described with reference to elements other figures in the disclosure. For example, AP **1110** can be AP **160** or one of PE AP **110a-110c** of FIG. **1**, and STA **1120** can be STA **130**, STA **180**, STA **170**, or one of PE non-AP STA **120a-120c** of FIG. **1**.

(109) During operations, the random MAC address scheme includes 46 bits that are randomly selected. STA **1120** experiences a collision only if both AP **1110** and STA **1120** individual addresses collide. The receiver checks the transmitter address and receiver address and if the STA is the receiver and associated AP is the transmitter, then the STA will receive a frame that is not targeted to itself. This is very rare situation. An AP MAC address in a group address can experience a collision (e.g., associated AP **1110** has the same MAC address as other AP (not shown).)

(110) To avoid MAC address collisions: STA **1120** may signal colliding MAC Addresses to AP **1110**. In some embodiments, STA **1120** may propose a new MAC address for itself, STA **1120**. In some embodiments, STA **1120** may propose that AP **1110** change AP **1110**'s MAC address, if AP **1110**'s MAC address collides with other MAC addresses. AP **1110** or a server (not shown) may store the MAC addresses currently in use and/or MAC addresses to be used in the future, and determine whether the MAC addresses currently in use and MAC addresses to be used in the future will collide. In some embodiments, AP **1110** may request that STA **1120** change STA **1120**'s MAC address to avoid a MAC address that is already in use.

(111) Example **1100** illustrates signaling for MAC address collision detection and avoidance.

(112) At **1130**, STA **1120** has associated with AP **1110** and has configured individual address sets and group address sets.

(113) At **1140**, STA **1120** detects a MAC address in the channel (e.g., link) that will collide with STA **1120**'s MAC address in an address set that is going to be used in the future. STA **1120** reports the collision to the the associated AP, AP **1110**. The report can include a proposed a new MAC address for STA **1120**. (See **1150** below.)

(114) At **1150**, STA **1120** can transmit a Robust MGMT frame that includes an Address Collision

Notification that can include the following: Colliding STA **1120** MAC address, proposed new STA **1120** MAC address, and a time when the proposed new STA **1120** MAC address is in use.

(115) At **1160**, AP **1110** can transmit a Robust MGMT frame that includes an Address Collision Notification that can include an indication of acceptance (or not).

(116) At **1170**, STA **1120** proceeds to operate with the new MAC address. (See **1160** above.)

(117) FIG. **12** illustrates example method **1200** for data transmission with randomized address sets, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **12** may be described with reference to elements other figures in the disclosure. In some embodiments, transmitter **1230** can be AP **160** or one of PE AP **110a-110c** of FIG. **1**, and receiver **1240** can be STA **170**, or one of PE non-AP STA **120a-120c** of FIG. **1**. In some embodiments, receiver **1240** can be AP **160** or one of PE AP **110a-110c** of FIG. **1**, and transmitter **1230** can be STA **130**, STA **180**, STA **170**, or one of PE non-AP STA **120a-120c** of FIG. **1**.

(118) In method **1200**, for convenience and not a limitation, transmitter **1230** can be AP **410** of FIG. **4A** and receiver **1240** can be associated STA **420** (also referred to as STA **420**) of FIG. **4A**. AP **410** can receive data corresponding to an Internet/Application, encrypt the data, and apply an individual address set as described herein, where the individual address set modifies only the addresses and parameters transmitted over-the-air (OTA). STA **420** can receive the data, and send block acknowledgement (BA) using the individual address set information. The individual address set application is reversed before the MPDU is decrypted. The MPDU is decrypted and the data sent to the corresponding Internet/Application at **1250**. Details of method **1200** are provided below.

(119) At **1210**, data corresponding to Internet/Application is generated and sent/delivered through Internet to AP **410** for ultimate transmission to Internet/Application at **1250**.

(120) At **1232**, AP **410** performs aggregated MAC Service Data Unit (A-MSDU) aggregation to form a MAC Protocol Data Unit (MPDU). AP **410** assigns a packet number (PN) corresponding to the MPDU and encrypts a portion of the MPDU (e.g., a payload portion of the MPDU).

(121) At **1234**, a sequence number (SN) corresponding to the encrypted MPDU is set.

(122) At **1236**, AP **410** applies an individual address set as described in Table 1. Individual Address such as Set **1 411** of FIG. **4**. Accordingly, the address fields in the MAC header can be updated such that the Transmitting Address (TA) corresponds to the BSSID.sub.unicast of AP **410** of the individual address set **411**, and the Receiving Address (RA) corresponds to STA Link Address.sub.unicast of STA **420**. In addition, AP **410** can create an over-the-air (OTA) packet number (PN.sub.OTA) that is different than the PN corresponding to the MPDU, where the PN.sub.OTA is transmitted OTA at **1250**. The PN.sub.OTA=PN+PN.sub.Offset, where the offset PN (PN.sub.Offset) is the PN Offset.sub.unicast of individual address set **411**. AP **410** can also create an over-the-air (OTA) sequence number (SN.sub.OTA) that is different than the SN corresponding to the MPDU (e.g., see **1234** above), wherein the SN.sub.OTA is transmitted OTA at **1250**. The SN.sub.OTA=SN+SN.sub.Offset, where the offset SN (SN.sub.Offset) is the SN Offset (TID).sub.unicast of individual address set **411**.

(123) At **1238**, AP **410** transmits the corresponding data from the transmission queue in transmission OTA **1250** to receiver **1240** (STA **420**).

(124) At **1242**, STA **420** determines whether the transmission is intended for STA **420** by determining whether the RA and TA correspond to individual address set **411**.

(125) At **1244**, in a receive buffer of STA **420**, STA **420** generates and transmits block acknowledgement (BA) with the received values. Subsequently, STA **420** restores the MPDU parameters using the individual address set **411** parameters. For example, STA **420** can determine the PN using PN.sub.OTA of PN.sub.Offset of the individual address profile **411**, and determine the SN using the SN.sub.OTA and SN.sub.Offset of individual address set **411**, where the PN and the SN correspond to the MPDU. The PN and SN can be determined by the following equations:  $PN = PN.sub.OTA - PN.sub.Offset$  and  $SN = SN.sub.OTA - SN.sub.Offset$ .

(126) At **1246**, STA **420** can reorder the frames based on the SN.

(127) At **1248**, STA **420** can decrypt the encrypted portion of the MPDU, check the PN order of the MPDUs, and check for each MPDU whether the Source Address (SA) and Destination Address (DA) are received from the secure A-MSDU.

(128) At **1250**, the data is sent to the corresponding Internet/Application.

(129) FIG. **13A** illustrates diagram **1300** showing data that is delivered to Galois/counter mode (GCM) encryption as described in IEEE P802.11REVme. Diagram **1300** includes construct additional authentication data (AAD) **1320**, construct GCM protocol (GCMP) header **1330**, and GCM encryption **1310** to form an encrypted MPDU. The GCM Headers include the PN of the MPDU. The PN number of a transmitter is increasing monotonically and the PN can be used to trace the transmitter as shown in FIG. **14A** illustrating example **1400** of an expanded GCMP MPDU. To protect identities of a STA (or an AP), the individual address set or group address set should modify the PN number. In some embodiments, an individual address set or a group address set includes an offset PN value that is different than the PN so that tracking between address sets is not possible.

(130) FIG. **13B** illustrates example **1350** of an encryption block diagram supporting randomized address sets, according to some embodiments of the disclosure. Some embodiments improve privacy of MAC addresses and thus, wireless communications while minimizing impacts to encryption processes. For example, PN.sub.OTA that is transmitted OTA is added after the encryption of the A-MSDU. In addition, additional authentication data (AAD) construction is done with predefined addresses of the STA and the AP. This means that encryption uses the STA and AP addresses that are not transmitted OTA. The OTA transmitted address belonging to an individual address set or a group address set is changed first to the non-changing static address of the STA and AP. The MAC Addresses and SN of the OTA transmitted packet are changed and the updated MAC header is prepended to the output of GMC encryption module **1310**. The updated operations in a transmitter (e.g., transmitter **1230** of FIG. **12**) are shown in example **1350** below as follows: At **1362** the PN.sub.OTA is calculated by adding PN.sub.Offset to PN. At **1364**, the PN.sub.OTA is inserted to GCMP Header (shown in FIG. **14A**). At **1380**, SN, transmitter address (TA), and receiver address (RA) of the MAC header are modified for OTA transmission.

(131) Example **1350** illustrates how parameters (e.g., PN.sub.Offset, SN.sub.Offset) in individual address set profiles and/or group address set profiles can be used to generate over-the-air (OTA) parameters (e.g., PN.sub.OTA, SN.sub.OTA). Example **1350** illustrates at **1360** of PN.sub.offset being added at **1362** and construct GCM header **1364** so that the offset PN can be calculated as:  $PN.sub.OTA = PN + PN.sub.Offset$

(132) The AAD is used in encryption (for transmission) and decryption (for reception) of a frame that includes the A-MSDU. FIG. **14B** illustrates example **1450** of an AAD for a protocol version 0 (PV0) MPDU. The AAD includes an MPDU Frame Control field, addresses of the encrypted/decrypted frame, MPDU Sequence control fields (bits 0-3 are present, other bits are masked to 0), QoS Control field (bits 0-3 and bit 7 if A-MSDU capable STA are present, other bits are masked to 0). If either of To Distributed System (DS) or From DS subfields of the MAC header of the MPDU is set to 1, and the MPDU is an individually addressed data frame between an AP MLD and a non-AP MLD associated with the AP MLD, then A1 is set to the MLD MAC address of the intended receiver MLD of the MPDU and A2 is set to the MLD MAC address of the transmitting MLD of the MPDU. Otherwise, A1 is set to the MPDU Address 1 field, and A2 is set to the MPDU Address 2 field. If MPDU Address 3 field is BSSID and the MPDU is an individually addressed data frame between an AP MLD and a non-AP MLD associated with the AP MLD, then A3 is set to the MLD MAC address of the AP MLD, where the corresponding AP with the BSSID is affiliated with the AP MLD. Otherwise, A3 is set to the MPDU Address 3 field, and A4, if present, is set to the MPDU Address 4 field. At **1380**, OTA SN of the MAC header is generated as  $SN.sub.OTA = SN + SN.sub.Offset$ .

(133) FIG. **22A** illustrates diagram **2200** showing decryption of encrypted MPDU that is delivered

to Galois/counter mode (GCM) decryption module as described in IEEE P802.11REVme. Diagram **2200** illustrates parsing the input encrypted MPDU to construct AAD and nonce values. At **2220**, AAD is constructed from the MPDU header of the encrypted MPDU. At **2230**, nonce is constructed from the A2 and PN fields. The constructed AAD, data (which is the encrypted frame body of the plaintext MPDU), message integrity check (MIC), and the constructed nonce are input to GCM decryption module **2210** to generate the plaintext data. The received MPDU header and the MPDU plain text from the GCM decryption function are concatenated to form a plaintext MPDU.

(134) FIG. **22B** illustrates example **2270** of a decryption block diagram supporting randomized address sets, according to some embodiments of the disclosure. At **2250**, the receiver verifies whether the MAC addresses of the MPDU match with the link addresses of the receiver. At **2260**, the parameters in the MAC header that were modified at **1380** of the example **1350** are restored to the original values. The SN and PN are restored by subtracting the offsets added at the transmitter ( $SN = SN.sub.OTA - SN.sub.Offset$  from Address Set and  $PN = PN.sub.OTA - PN.sub.Offset$  from Address Set). Further, at **2260**, the STA link address can be set to STA MLD address and the AP link address is set to AP MLD address. The input encrypted MPDU with updated MAC header is parsed to construct AAD and nonce values at **2220** and **2230**, respectively. The constructed AAD, the data (which is the encrypted frame body of the plaintext MPDU), the message integrity check (MIC), and the constructed nonce are input to GCM decryption module **2210** to generate the plaintext data. The received MPDU header and the MPDU plain text from the GCM decryption function are concatenated to form a plaintext MPDU.

(135) In some embodiments, when an individual address set or a group address set is in use the MAC addresses of packets received OTA are changed back to MAC-SAP addresses of the AP and the STA. In some embodiments, the legacy MAC Address split into 3 addresses. These addresses are the same as in MLD MAC Address. The MAC-SAP address is used in all encryption and decryption operations to avoid changes to encryption and decryption procedures.

(136) The receiver checks the addresses of a received frame before applying the AAD parameters. The check ensures that the received frame is addressed according to address set rules (see Table 2. Rules for APs and STAs that use Address Randomization) that are currently in use. In some embodiments, for a MLD (e.g., 802.11be case) the OTA MLD addresses (described below at FIG. **17**) are in use, and AAD obtaining has been changed for 802.11be MLDs. Some embodiments change the link addresses to the MLD-SAP addresses. The use of the same MLD-SAP address ensures that encrypted MPDU may be transmitted over any link by changing only the address set specific parameter values and without need to redo the encryption (e.g. decrypt and re-encrypt) the MPDU. The receiver checks that the MAC Addresses of an MPDU received OTA match with the address profile in use, but the AAD used in the encryption uses the initial MAC Addresses.

(137) Some embodiments include rules to randomize selected parameters as shown below in Table 5. Rules to Randomize Selected Parameters.

(138) TABLE-US-00005 TABLE 5 Rules to Randomize Selected Parameters Randomized Are Collisions Parameter Uniqueness Randomization Procedure Possible? MAC Unique for MAC address the individual/group bit not Yes, a collision address operating randomized The Local/Global bit is set to Local needs to be channels value. All other 46 bits are randomized solved Association Unique The AP allocates AID values for STAs. AP shall No, AP ID (AID) within AP not allocate a value that is used for group frames allocates all indication. AP may select the values so that bits values used in a traffic indication map (TIM) element is efficient (the size of TIM element is minimized), e.g., AP may select a range of values and randomly allocate values within this range to the AP's associated STAs Color Value Semi- The Color value is randomly selected. AP has Yes, a collision unique for Color value that is used for UL and DL may be ignored operating transmissions to AP channels Sequence Unique The initial SN is randomized. AP may select No. AP Number within AP sequence number offset for each SN in use. The manages the (SN) MLD, SN value is calculated as  $SN.sub.OTA = (SN + SN \text{ that it SNS, TID } SN.sub.OFFSET) \text{ Mod } 4096$

transmits and STA manages receiver SN that it transmits Unique The initial Packet Number is randomized. The PN No. AP Number within AP is 6 octet long value that monotonically increases. manages the (PN) MLD, TID When new PN.sub.OFFSET is PN.sub.OTA can be calculated: PN that it and PN.sub.OTA = (PN + PN.sub.OFFSET)Mod 2.sup.63, transmits and receiver where PN.sub.OFFSET is a random integer(2.sup.64) AND STA manages  $0 < PN < MAX(2.sup.64)$  PN that it The PN.sub.OFFSET is a random signed 64 bit long transmits integer. Time Unique The lowest 56 bits of the TSF value are No. this is AP Synchronization within AP randomized when AP is created or if an AP specific value Function changes the AP's MAC addresses (TSF)

(139) In some embodiments, PE MLDs implement two levels of MAC address randomization. In a first level of MAC address randomization, BSS/AP link specific addresses can be randomized. In other words, addresses corresponding to a link of an MLD are randomized separately from other links of the MLD. Thus, each link may have own individual and group address sets. And, each link may have a separate algorithm or algorithm parameters to randomly select the link-specific MAC addresses. This is similar to the examples of systems **400** and **500** of FIGS. **4A** and **5A** for single link devices.

(140) FIG. **15** illustrates example privacy enhanced (PE) multi-link device (MLD) system **1500** supporting address randomization schemes, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **15** may be described with reference to elements from FIG. **1**. For example, PE AP MLD **1510** includes 3 affiliated PE APs: PE AP1 **1511**, PE AP2 **1513**, and PE AP3 **1515** can be PE AP MLD **110** that includes affiliated PE AP **110a-110c** of FIG. **1**. PE non-AP MLD **1520** includes 3 affiliated PE non-AP STAs: PE non-AP STA1 **1521**, PE non-AP STA2 **1523**, PE non-AP STA3 **1525** that can be PE non-AP MLD **120** with affiliated PE non-AP STA **120a-120c** of FIG. **1**. PE AP MLD **1510** communicates over corresponding links: link **1 1530**, link **2 1535**, and link **3 1540** with PE non-AP MLD **1520**.

(141) For example, PE AP1 **1511** operates BSS1 and communicates over link **1 1530** to PE non-AP STA1 **1521**. PE AP1 **1511** can establish multiple individual address sets with PE non-AP STA1 **1521** where the multiple individual address sets identified as Unicast Address Sets **1** in system **1500** can be used in communications over link **1 1530**. In addition, multiple group address sets identified as Groupcast Address Sets **1** can be established for communications over link **1 1530**. PE AP2 **1513** operates BSS2 and communicates over link **2 1535** to PE non-AP STA2 **1523**. PE AP2 **1513** can establish multiple individual address sets with PE non-AP STA2 **1523** where the multiple individual address sets identified as Unicast Address Sets **2** in system **1500** can be used in communications over link **2**. Multiple group address sets identified as Groupcast Address Sets **2** can be established for communications over link **2 1533**. And, PE AP3 **1515** operates BSS3 and communicates over link **3 1540** to PE non-AP STA3 **1525**. PE AP3 **1515** can establish multiple individual address sets with PE non-AP STA3 **1525** where the multiple individual address sets identified as Unicast Address Sets **3** in system **1500** can be used in communications over link **3**. Multiple group address sets identified as Groupcast Address Sets **3** can be established for communications over link **3 1540**.

(142) In a second level of MAC address randomization, MLD addresses as well as MLD-level identifiers and parameters are randomized at the MLD level. In other words, there are no common unencrypted MLD addresses or MLD identifiers and parameters that are transmitted over the air. Having MLD level addresses, identifiers, and parameters randomized at the MLD level ensures that PE APs affiliated with a PE AP MLD may operate independently, and PE non-AP STAs affiliated with a PE non-AP MLD may operate independently.

(143) FIG. **16** illustrates example PE MLD system **1600** including address and identifier randomization, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **16** may be described with reference to elements from FIG. **15**. For example, PE AP MLD **1610** can be PE AP MLD **1510** and PE non-AP MLD **1620** can be PE non-AP MLD

**1520** of FIG. **15**. System **1600** includes PE AP MLD **1610** that includes 3 affiliated PE APs: PE AP1 **1611**, PE AP2 **1613**, and PE AP3 **1615** that communicate over corresponding links: link **1 1630**, link **2 1635**, and link **3 1640** with PE non-AP MLD **1620**. PE non-AP MLD **1620** includes 3 affiliated PE non-AP STAs: PE non-AP STA1 **1621**, PE non-AP STA2 **1623**, PE non-AP STA3 **1625**.

(144) PE AP MLD **1610** MLD-level parameters are randomized and used in the 3 affiliated PE APs. These MLD-level parameters have separate values in each of affiliated PE AP1 **1611**, PE AP2 **1613**, and PE AP3 **1615**, so that an attacker (e.g., a bad actor) may not know in which links (e.g., link **1 1630**, link **2 1635**, and link **3 1640**) PE AP MLD **1610** operates. Each of affiliated PE AP1 **1611**, PE AP2 **1613**, and PE AP3 **1615** can maintain separately and hide MLD-level parameters that include but are not limited to: MLD address, TSF, AID, PN, Sequence Number Spaces (SNS): per STA & DL TID, group frames, MGMT frames and/or legacy frames. PE AP MLD **1610**'s MLD address can be encrypted so that attackers do not detect the affiliated PE AP1 **1611**, PE AP2 **1613**, and PE AP3 **1615** that belong to PE AP MLD **1610**. SN and PN counters are maintained at the MLD level. Thus, PE AP MLD **1610** should modify SN and PN packet values for each link separately. Each link (e.g., link **1 1630**, link **2 1635**, and link **3 1640**) may have a corresponding TSF value. The TSF values should be changed independently from other link-specific TSF values of other links to make affiliated PE AP tracing difficult.

(145) PE non-AP MLD **1620** MLD-level parameters are used in 3 affiliated PE non-AP STAs. These MLD-level parameters have separate values in each of affiliated PE non-AP STA1 **1621**, PE non-AP STA2 **1623**, PE non-AP STA3 **1625**, so that an attacker may not know in which links the PE non-AP MLD **1620** operates. Each of affiliated PE non-AP STA1 **1621**, PE non-AP STA2 **1623**, PE non-AP STA3 **1625** can maintain separately and hide MLD-level parameters including but not limited to: MLD Address, PN, SNS: UL per TID. PE non-AP MLD **1620** MLD address should be encrypted so that attackers do not detect the affiliated PE non-AP STA1 **1621**, PE non-AP STA2 **1623**, PE non-AP STA3 **1625** that belong to PE non-AP MLD **1620**.

(146) FIG. **17** illustrates example **1700** of multiple MLD address types for address randomization, according to some embodiments of the disclosure. In some embodiments, an MLD address transmitted over-the-air (OTA) can be changed and randomized. Example **1700** includes MLD address **1710** that can be an IEEE 802.11be MLD address. MLD address **1710** can be one of 3 different addresses: i) Unique MLD address **1730** that identifies the MLD (e.g., PE AP MLD or PE MLD) in authentication and association. Unique MLD address **1730** is a constant value for a PE MLD and cannot be changed; ii) MAC service access point (SAP) address **1740** that can be a MAC address that identifies the non-AP MLD toward the Internet (e.g., is visible to APs that are Ethernet connected to the Internet. This MAC address may be used in the MPDUs encryption and decryption. The encryption is done with the SAP address and after encryption, the MAC addresses in OTA packet are changed to OTA MAC Addresses. Similarly in the decryption, the OTA addresses are first checked to match with link specific address and then the SAP address is used in the decryption. MAC SAP address **1740** is a constant value and cannot be changed; and iii) OTA MLD address **1720** that may be transmitted in Address **3** of a data frame. (See IEEE P802.11REVme.) In some embodiments, a PE non-AP MLD can change and encrypt an OTA MLD address value. In some embodiments, OTA MLD address **1720** can be the same as MAC SAP address **1740**. OTA MLD address **1720** may be the same as MAC SAP address **1740** when a portion of an MPDU comprising an MLD address is encrypted.

(147) A PE AP MLD and a PE non-AP MLD have also link specific addresses that are used in each link separately. The link specific addresses are used to identify the PE AP and the PE non-AP STA in the link. Each PE AP in the PE AP MLD shall have unique link specific MAC address values. PE non-AP STAs in a PE non-AP MLD may have the same link MAC Address in different links. The individual address set defines the link specific MAC Addresses that are used for individual frames transmission. Similarly, the group address set defined link address that a PE AP uses to transmit the

group frames.

(148) FIG. **18A** illustrates example **1800** of a data transmission supporting PE MLD randomized address, according to some embodiments of the disclosure. Example **1800** illustrates data transmission of a PHY protocol data unit (PPDU) including preamble **1805**, and aggregate MPDU (A-MPDU) subframes **1810a-1810c** that may be transmitted OTA.

(149) FIG. **18B** illustrates example MPDU **1820** of a portion of an A-MPDU subframe **1810** including unencrypted A-MPDU subframe header **1822** and MAC header **1824**, encrypted A-MSDU subframe **1850**, and unencrypted frame check sequence **1826**, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **18B** may be described with reference to elements from other figures in the disclosure. For example, example MPDU **1820** can be created by PE AP MLD **1610** and/or PE non-AP MLD **1620** of FIG. **16**. In some embodiments, MPDU **1820** can be a portion of A-MPDU subframe **1810** of FIG. **18A**, where A-MPDU **1810** may also include an MPDU delimiter field and variable length padding.

(150) FIG. **18C** illustrates basic A-MSDU subframe structure **1850** that is encrypted as shown in A-MPDU subframe **1820**. A-MSDU subframe structure includes A-MSDU subframe header **1830**, an MSDU of variable length and variable length padding. In some embodiments, A-MSDU subframe header **1830** may comprise encrypted MLD addresses and unencrypted MAC header **1824** may comprise link specific MAC addresses. For example, MLD Addresses can be present in a Source Address (SA) or a Destination Address (DA) of A-MSDU subframe header **1830**. In some embodiments, OTA MLD address **1720** can be present in SA or DA of A-MSDU subframe header **1830**. In some embodiments, OTA MLD address **1720** present in SA or DA of A-MSDU subframe header **1830** can be same as MAC SAP address **1740**. Thus, PE AP MLD **1610** and PE non-AP MLD **1620** may encrypt A-MSDU subframe header **1830** to protect an MLD address that may be in the SA or DA fields. The SA and DA may be addresses in Ethernet, Wi-Fi mesh addresses or MLD addresses, depending on the final destination of the frame. This is different than transmissions that typically transmit A-MSDU subframe header **1830** unencrypted.

(151) FIG. **19** illustrates example **1900** of changing an OTA MLD MAC address for group addressed PPDU's, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **19** may be described with reference to elements from FIG. **15**. For example, PE AP MLD **1910** can be PE AP MLD **1510** and PE non-AP MLD **1920** can be PE non-AP MLD **1520** of FIG. **15**. System **1900** includes PE AP MLD **1910** that includes 2 affiliated PE APs: PE AP1 **1912** and PE AP2 **1914** that communicate over corresponding links with PE non-AP MLD **1920**. PE non-AP MLD **1920** includes 2 affiliated PE non-AP STAs: PE non-AP STA1 **1922** and PE non-AP STA2 **1924**.

(152) Legacy STA **1930** may not be capable to receive encrypted A-MSDU aggregated group frames. If PE AP MLD **1910** has legacy STA **1930** associated in any affiliated PE AP (e.g., PE AP1 **1912**), an OTA MLD address may need to be randomized to protect privacy of PE AP MLD **1910**. When group addressed frames are transmitted by all affiliated PE APs of a PE AP MLD (e.g., PE AP 1 **1912** and PE AP 2 **1914**), encrypting MLD addresses in one affiliated PE AP (e.g., PE AP 1 **1912**) of PE AP MLD **1910** may not protect the MLD address transmitted in other affiliated PE APs (e.g., PE AP 2 **1914**) of PE AP MLD **1910**.

(153) In some embodiments, PE non-AP MLD **1920** may change a corresponding OTA MLD address as part of the unicast address set. In some embodiments, PE AP MLD **1910** may change a corresponding OTA MLD address as part of the groupcast address set. For example, the OTA MLD address change may be performed via signaling for configuring and updating link-specific address sets as described in FIG. **8**, **9**, or **20**. At all times, PE AP MLD **1910** should have one corresponding OTA MLD in use and PE non-AP MLD **1920** should have one corresponding OTA MLD in use.

(154) FIG. **20** illustrates example **2000** of signaling for configuring joint algorithms that determine address sets for MLDs and signaling for address collision notification, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **20** may be

described with reference to elements from FIG. 1. For example, PE AP MLD **2010** can be PE AP MLD **110**, affiliated PE AP1 **2010a** and PE AP2 **2010b** can be affiliated PE AP **110a** and PE AP **110b**, PE non-AP MLD **2020** can be PE non-AP MLD **120**, and affiliated PE non-AP STA1 **2020a** and PE non-AP STA2 **2020b** can be affiliated PE non-AP STA **120a** and PE non-AP STA **120b** of FIG. 1.

(155) The Association Request may also contain the PE non-AP MLD SAP MAC Address that is used in frames encryption, and it may include the PE non-AP MLD's MLD address that is used for authentication and association. Similarly, the Association Response may also contain the PE AP MLD SAP MAC Address and PE AP MLD's MLD address that is used in authentication and association.

(156) In some embodiments, individual address sets and group address sets are signaled for all links in the setup signaling. Each link may have independent address change schedules and different random address values. MLD Addresses and MLD level parameters are also setup for PE AP MLD **2010** and PE non-AP MLD **2020**. The Address collision notification may be transmitted over any link and it may report collision over any link (e.g., link **1** or link **2** of example **2000**).

(157) During association, joint algorithms to configure and update the address set parameters can be arranged. In association signaling, PE AP MLD **2010** and PE non-AP MLD **2020** can agree on set of joint algorithms to calculate link-specific individual address sets and link-specific group address sets. The joint algorithms may also configure address set transition times and the number of address sets in use. Further, the joint algorithms may be different for each link of the multiple links of the MLDs. The communication may occur over one link of multiple links between an affiliated PE AP (e.g., PE AP1 **2010a**) and an affiliated PE non-AP STA (e.g., PE non-AP STA1 **2020a**). PE AP MLD **2010** may change one or all of the joint algorithms or one or more parameter values used for link-specific address sets (e.g., individual address sets or group address sets). For example, if a STA (not shown) has disassociated from PE AP1 **2010a**, a change of the groupcast address set algorithm ensures that only associated STAs (e.g., PE non-AP STA1 **2020a**) can know the next address of PE AP1 **2010a**. Alternatively, PE AP1 **2010a** can maintain the algorithms for group address sets, so that STAs that reassociate with PE AP1 **2010a** may calculate the current PE AP1 **2010a** parameters and discover PE AP1 **2010a**.

(158) At **2030**, PE AP1 **2010a** may transmit a Beacon frame that may signal support for address randomization and a minimum number of individual address sets in association. The Beacon frame can include RSNE that includes an indication of: PASN protocol, FT, AKM, RSNXE, MDE, and/or Address Randomization supported.

(159) At **2035**, authentication occurs between PE non-AP MLD **2020** and PE AP MLD **2010**.

(160) At **2040**, PE non-AP STA1 **2020a** transmits a PASN protected Association Request that proposes an individual address set algorithm for link **1** and link **2** (where the algorithms may be different per link) including: algorithm parameters, a random value, and MAC address seed. The Association Request can also include a proposed average duration for individual address sets, and other association parameters for link **1** and for link **2** (e.g., PHY & MAC capabilities of PE non-AP STA1 **2020a**).

(161) At **2045**, PE AP1 **2010a** can transmit a PASN protected Association Response that includes an indication of success (or not), an individual address algorithm for link **1** and link **2** and includes: algorithm parameters, a random value, a first AP MAC address seed, and/or individual address set start and end time seeds. The Association Response can also include a group address algorithm for link **1** and for link **2** and include a random value and/or a second AP MAC address seed, where the first AP MAC address seed are different. The Association Response can include other association parameters corresponding to link **1** and link **2** (e.g., PHY & MAC capabilities.)

(162) At **2050**, PE non-AP MLD **2020** has associated with PE AP MLD **2010** and has configured individual address sets and/or group address sets for each link as described in Table 1. Individual Address Set and/or Table 4. Group Address Set. Each link (e.g., PE non-AP STA1 **2020a** and PE

AP1 **2010a**) has a schedule for changing individual address sets and group address sets.

(163) At **2065**, PE non-AP STA2 **2020b** detects an address in the channel that will collide with a MAC address of PE non-AP STA2 **2020b** in an address set that is going to be used in the future. For example, PE non-AP STA2 **2020b** can inform PE non-AP MLD **2020** that causes PE non-AP STA1 **2020a** to report the collision to associated PE AP MLD **2010**. The report may include a proposed new MAC address for PE non-AP STA2 **2020b**.

(164) At **2070**, PE non-AP STA1 **2020a** can transmit a Robust MGMT frame that includes an Address Collision Notification that can include the following: Colliding PE non-AP STA2 **2020b**'s MAC address, proposed new MAC address for PE non-AP STA2 **2020b**, and a time when the proposed new MAC address for PE non-AP STA2 **2020b** is in use.

(165) At **2080**, PE non-AP STA1 **2020a** can transmit a Robust MGMT frame that includes an Address Collision Notification that can include an indication of acceptance (or not).

(166) FIG. **21** illustrates example method for data transmission between PE MLDs, according to some embodiments of the disclosure. For explanation purposes and not a limitation, FIG. **21** may be described with reference to elements other figures in the disclosure. In some embodiments, transmitter **2130** can be PE AP **110** that includes 3 affiliated PE APs: PE AP **110a-110c** of FIG. **1**, and receiver **2140** can be PE non-AP MLD **120** that includes 3 affiliated PE non-AP STAs: PE non-AP STA **120a-120c** of FIG. **1**. In some embodiments, receiver **2140** can be PE AP **110** that includes 3 affiliated PE APs: PE AP **110a-110c** of FIG. **1**, and transmitter **2130** can be PE non-AP MLD **120** that includes 3 affiliated PE non-AP STAs: PE non-AP STA **120a-120c** of FIG. **1**.

(167) In method **2100**, for convenience and not a limitation, transmitter **2130** can be PE AP MLD **1510** of FIG. **15**, where PE AP MLD **1510** includes 3 affiliated PE APs: PE AP1 **1511**, PE AP2 **1513**, and PE AP3 **1515**. Receiver **2140** can be associated PE non-AP MLD **1520** of FIG. **15**, where PE non-AP MLD **1520** includes 3 affiliated PE non-AP STAs: PE non-AP STA1 **1521**, PE non-AP STA2 **1523**, PE non-AP STA3 **1525**. PE AP MLD **1510** can receive data corresponding to an Internet/Application, encrypt the data, and apply an individual address set as described herein, where the individual address set modifies only the addresses and parameters transmitted over-the-air (OTA). PE non-AP MLD **1520** can receive the data, and send block acknowledgement (BA) using the individual address set information. The individual address set application is reversed before the MPDU is decrypted. The MPDU is decrypted and the data sent to the corresponding Internet/Application at **2150**. Details of method **2100** are provided below.

(168) At **2110**, data corresponding to Internet/Application is generated and send to PE AP MLD **1510** for ultimate transmission to Internet/Application at **2150**.

(169) At **2132**, PE AP MLD **1510** performs aggregated MAC Service Data Unit (A-MSDU) aggregation to form a MAC Protocol Data Unit (MPDU). PE AP MLD **1510** assigns a packet number (PN) corresponding to the MPDU and encrypts the MPDU.

(170) At **2134**, a sequence number (SN) corresponding to the encrypted MPDU is set.

(171) At **2136a**, PE AP MLD **1510** selects PE AP1 **1511** to transmit the encrypted MPDU, and applies an individual address set as described in Table 1. Individual Address Set such as Set **1** (e.g., **411** of FIG. **4**) that corresponds to PE AP1 **1511**. Accordingly, the Transmitting Address (TA) corresponds to the BSSID.sub.unicast of PE AP1 **1511** of the individual address set, and the Receiving Address (RA) corresponds to STA Link Address.sub.unicast of PE non-AP STA1 **1521**. In addition, PE AP1 **1511** can create an over-the-air (OTA) packet number (PN.sub.OTA) that is different than the PN corresponding to the MPDU, where the PN.sub.OTA is transmitted OTA at **2150a**. The PN.sub.OTA=PN+PN.sub.Offset, where the offset PN (PN.sub.Offset) is the PN Offset.sub.unicast of the individual address set. PE AP1 **1511** can also create an over-the-air (OTA) sequence number (SN.sub.OTA) that is different than the SN corresponding to the encrypted MPDU, where the SN.sub.OTA is transmitted OTA at **2150a**. The SN.sub.OTA=SN+SN.sub.Offset, where the offset SN (SN.sub.Offset) is the SN Offset (TID).sub.unicast of the individual address set. Similar processes occur on the various links at **2136b** and **2136c** when PE AP MLD **1510**

selects PE AP2 **1513** and PE AP3 **1515**, respectively.

(172) At **2138a**, PE AP1 **1511** transmits the corresponding data from the transmission queue OTA in a transmission OTA **2150a** to receiver **2140** corresponding to PE non-AP STA1. Similar processes occur on the various links at **2138b** and **2138c** when PE AP MLD **1510** selects PE AP2 **1513** and PE AP3 **1515**, respectively.

(173) At **2142a**, PE non-AP STA1 determines whether the transmission is intended for PE non-AP STA1 by determining whether the RA and TA correspond to the individual address set. Similar processes occur on the various links at **2142b** and **2142c** when PE AP MLD **1510** selects PE AP2 **1513** and PE AP3 **1515**, respectively. For example, the individual address sets would identify PE non-AP STA2 **1523** and PE non-AP STA3 **1525**.

(174) At **2144a**, in a receive buffer of PE non-AP STA1, PE non-AP STA1 generates and transmits block acknowledgement (BA) with the received values. Subsequently, PE non-AP STA1 restores the MPDU parameters using the individual address set parameters. For example, PE non-AP STA1 can determine the PN using PN.sub.OTA of PN.sub.Offset of the individual address profile, and determine the SN using the SN.sub.OTA and SN.sub.Offset of individual address set, where the PN and the SN correspond to the MPDU. The PN and SN can be determined by the following equations:  $PN = PN.sub.OTA - PN.sub.Offset$  and  $SN = SN.sub.OTA - SN.sub.Offset$ . Similar processes occur on the various links at **2144b** and **2144c** when PE AP MLD **1510** selects PE AP2 **1513** and PE AP3 **1515**, respectively.

(175) At **2146**, PE non-AP MLD **1520** can reorder the frames based on the SN.

(176) At **2148**, PE non-AP MLD **1520** can decrypt the encrypted MPDU, check the PN order of the MPDUs, and check for each MPDU whether the Source Address (SA) and Destination Address (DA) are received from the secure A-MSDU.

(177) At **2150**, the data is sent to the corresponding Internet/Application.

(178) Various embodiments can be implemented, for example, using one or more well-known computer systems, such as computer system **2200** shown in FIG. 22. Computer system **2200** can be any well-known computer capable of performing the functions described herein. For example, and without limitation, PE AP MLD **110**, PE AP **110a-110c**, PE non-AP MLD **120**, PE non-AP STA **120a-120c**, STA **130**, STA **170**, STA **180**, and AP **160** of FIG. 1, system **200** of FIG. 2, system **400** and example **450** of FIGS. 4A and 4B, system **500** and example **550** of FIGS. 5A and 5B, examples **600**, **700**, **800**, **900**, **1000**, **1100**, **1200**, **1350**, **1500**, **1600**, **1700**, **1800**, **1810a**, **1900**, **2000**, and **2100** of FIGS. 6-12, 13B, 15-17, 18A, 18B, and 19-21 (and/or other apparatuses and/or components shown in the figures) may be implemented using computer system **2300**, or portions thereof.

(179) Computer system **2300** includes one or more processors (also called central processing units, or CPUs), such as a processor **2304**. Processor **2304** is connected to a communication infrastructure **2306** that can be a bus. One or more processors **2304** may each be a graphics processing unit (GPU). In an embodiment, a GPU is a processor that is a specialized electronic circuit designed to process mathematically intensive applications. The GPU may have a parallel structure that is efficient for parallel processing of large blocks of data, such as mathematically intensive data common to computer graphics applications, images, videos, etc.

(180) Computer system **2300** also includes user input/output device(s) **2303**, such as monitors, keyboards, pointing devices, etc., that communicate with communication infrastructure **2306** through user input/output interface(s) **2302**. Computer system **2300** also includes a main or primary memory **2308**, such as random access memory (RAM). Main memory **2308** may include one or more levels of cache. Main memory **2308** has stored therein control logic (e.g., computer software) and/or data.

(181) Computer system **2300** may also include one or more secondary storage devices or memory **2310**. Secondary memory **2310** may include, for example, a hard disk drive **2312** and/or a removable storage device or drive **2314**. Removable storage drive **2314** may be a floppy disk drive, a magnetic tape drive, a compact disk drive, an optical storage device, tape backup device, and/or

any other storage device/disk.

(182) Removable storage drive **2314** may interact with a removable storage unit **2318**. Removable storage unit **2318** includes a computer usable or readable storage device having stored thereon computer software (control logic) and/or data. Removable storage unit **2318** may be a floppy disk, magnetic tape, compact disk, DVD, optical storage disk, and/or any other computer data storage device. Removable storage drive **2314** reads from and/or writes to removable storage unit **2318** in a well-known manner.

(183) According to some embodiments, secondary memory **2310** may include other means, instrumentalities or other approaches for allowing computer programs and/or other instructions and/or data to be accessed by computer system **2300**. Such means, instrumentalities or other approaches may include, for example, a removable storage unit **2322** and an interface **2320**. Examples of the removable storage unit **2322** and the interface **2320** may include a program cartridge and cartridge interface (such as that found in video game devices), a removable memory chip (such as an EPROM or PROM) and associated socket, a memory stick and USB port, a memory card and associated memory card slot, and/or any other removable storage unit and associated interface.

(184) Computer system **2300** may further include a communication or network interface **2324**. Communication interface **2324** enables computer system **2300** to communicate and interact with any combination of remote devices, remote networks, remote entities, etc. (individually and collectively referenced by reference number **2328**). For example, communication interface **2324** may allow computer system **2300** to communicate with remote devices **2328** over communications path **2326**, which may be wired and/or wireless, and which may include any combination of LANs, WANs, the Internet, etc. Control logic and/or data may be transmitted to and from computer system **2300** via communication path **2326**.

(185) The operations in the preceding embodiments can be implemented in a wide variety of configurations and architectures. Therefore, some or all of the operations in the preceding embodiments may be performed in hardware, in software or both. In some embodiments, a tangible, non-transitory apparatus or article of manufacture includes a tangible, non-transitory computer useable or readable medium having control logic (software) stored thereon is also referred to herein as a computer program product or program storage device. This includes, but is not limited to, computer system **2300**, main memory **2308**, secondary memory **2310** and removable storage units **2318** and **2322**, as well as tangible articles of manufacture embodying any combination of the foregoing. Such control logic, when executed by one or more data processing devices (such as computer system **2300**), causes such data processing devices to operate as described herein.

(186) Based on the teachings contained in this disclosure, it will be apparent to persons skilled in the relevant art(s) how to make and use embodiments of the disclosure using data processing devices, computer systems and/or computer architectures other than that shown in FIG. **23**. In particular, embodiments may operate with software, hardware, and/or operating system implementations other than those described herein.

(187) It is to be appreciated that the Detailed Description section, and not the Summary and Abstract sections, is intended to be used to interpret the claims. The Summary and Abstract sections may set forth one or more but not all exemplary embodiments of the disclosure as contemplated by the inventor(s), and thus, are not intended to limit the disclosure or the appended claims in any way.

(188) While the disclosure has been described herein with reference to exemplary embodiments for exemplary fields and applications, it should be understood that the disclosure is not limited thereto. Other embodiments and modifications thereto are possible, and are within the scope and spirit of the disclosure. For example, and without limiting the generality of this paragraph, embodiments are not limited to the software, hardware, firmware, and/or entities illustrated in the figures and/or

described herein. Further, embodiments (whether or not explicitly described herein) have significant utility to fields and applications beyond the examples described herein.

(189) Embodiments have been described herein with the aid of functional building blocks illustrating the implementation of specified functions and relationships thereof. The boundaries of these functional building blocks have been arbitrarily defined herein for the convenience of the description. Alternate boundaries can be defined as long as the specified functions and relationships (or equivalents thereof) are appropriately performed. In addition, alternative embodiments may perform functional blocks, steps, operations, methods, etc. using orderings different from those described herein.

(190) References herein to “one embodiment,” “an embodiment,” “an example embodiment,” or similar phrases, indicate that the embodiment described may include a particular feature, structure, or characteristic, but every embodiment may not necessarily include the particular feature, structure, or characteristic. Moreover, such phrases are not necessarily referring to the same embodiment. Further, when a particular feature, structure, or characteristic is described in connection with an embodiment, it would be within the knowledge of persons skilled in the relevant art(s) to incorporate such feature, structure, or characteristic into other embodiments whether or not explicitly mentioned or described herein.

(191) The breadth and scope of the disclosure should not be limited by any of the above-described exemplary embodiments, but should be defined only in accordance with the following claims and their equivalents.

(192) The present disclosure contemplates that the entities responsible for the collection, analysis, disclosure, transfer, storage, or other use of such personal information data will comply with well-established privacy policies and/or privacy practices. In particular, such entities should implement and consistently use privacy policies and practices that are generally recognized as meeting or exceeding industry or governmental requirements for maintaining personal information data private and secure. Such policies should be easily accessible by users, and should be updated as the collection and/or use of data changes. Personal information from users should be collected for legitimate and reasonable uses of the entity and not shared or sold outside of those legitimate uses. Further, such collection/sharing should only occur after receiving the informed consent of the users. Additionally, such entities should consider taking any needed steps for safeguarding and securing access to such personal information data and ensuring that others with access to the personal information data adhere to their privacy policies and procedures. Further, such entities can subject themselves to evaluation by third parties to certify their adherence to widely accepted privacy policies and practices. In addition, policies and practices should be adapted for the particular types of personal information data being collected and/or accessed and adapted to applicable laws and standards, including jurisdiction-specific considerations. For instance, in the US, collection of, or access to, certain health data may be governed by federal and/or state laws, such as the Health Insurance Portability and Accountability Act (HIPAA); whereas health data in other countries may be subject to other regulations and policies and should be handled accordingly. Hence different privacy practices should be maintained for different personal data types in each country.

## Claims

1. An access point (AP), comprising: a transceiver; and a processor coupled to the transceiver, configured to: establish two or more address profiles with a station (STA); establish a schedule for switching from a first address profile to a second address profile, wherein the first and second address profiles are of the two or more address profiles; encrypt an aggregated MAC Service Data Unit (A-MSDU); after the encryption, create an over-the-air (OTA) packet number (PN.sub.OTA) that is different than a packet number (PN) corresponding to the A-MSDU; and transmit, via the transceiver, a first data transmission using the first address profile, wherein the first data

transmission comprises the PN.sub.OTA, wherein the first address profile comprises an offset PN (PN.sub.Offset), and wherein the PN.sub.OTA=PN+PN.sub.Offset.

2. The AP of claim 1, wherein the processor is further configured to: switch from the first address profile to the second address profile based on the schedule; and transmit, via the transceiver, a second data transmission using the second address profile.

3. The AP of claim 1, wherein the schedule for switching from the first address profile to the second address profile is based on a randomized time synchronization function (TSF) parameter.

4. The AP of claim 1, wherein the processor is further configured to: establish new address profiles with the STA; establish a first time when the new address profiles are available for use; establish a second time when the AP begins operating on a different channel; and transmit on the different channel, via the transceiver, a second data transmission using a third address profile of the new address profiles, after the first and second times.

5. The AP of claim 4, wherein the processor is further configured to: determine an end time for the new address profiles, wherein the third address profile is randomly selected from the new address profiles before the end time.

6. The AP of claim 1, wherein the processor is further configured to: after the encryption, create an over-the-air (OTA) sequence number (SN.sub.OTA) that is different than a sequence number (SN) corresponding to the A-MSDU, wherein the first data transmission comprises the SN.sub.OTA, wherein the first address profile comprises an offset SN (SN.sub.Offset), and wherein the SN.sub.OTA=SN+SN.sub.Offset.

7. The AP of claim 1, wherein the processor is further configured to: after the encryption, apply an AP identifier of the first address profile, wherein the first data transmission comprises the AP identifier.

8. The AP of claim 1, wherein to establish the two or more address profiles, the processor is configured to: establish a joint algorithm with the STA; and use the joint algorithm to determine the first and the second address profiles as well as transition times for the schedule.

9. The AP of claim 8, wherein to establish the joint algorithm, the processor is further configured to: receive, via the transceiver, an individual address set algorithm, a MAC address seed, and a proposed address set average duration; and transmit in response to the reception, via the transceiver, an individual address set start time seed, an individual address set end time seed, a group address algorithm, and an AP MAC address seed.

10. The AP of claim 1, wherein the processor is further configured to: receive from the STA, via the transceiver, a notification of a colliding MAC address, wherein the notification comprises: the colliding MAC address, a proposed new MAC address for the STA, a time when the proposed new MAC address for the STA is in use, or a proposed new MAC address for the AP; and transmit to the STA, via the transceiver, a confirmation message corresponding to the notification.

11. A station (STA), comprising: a transceiver; and a processor coupled to the transceiver, configured to: establish two or more address profiles with an access point (AP); establish a schedule for switching from a first address profile to a second address profile, wherein the first and second address profiles are of the two or more address profiles; receive, via the transceiver, a first data transmission comprising a first receiving address (RA) corresponding to the first address profile; and determine a packet number (PN) using an over-the-air (OTA) packet number (PN.sub.OTA) of the first data transmission and an offset PN (PN.sub.Offset) of the first address profile, wherein the PN corresponds to an encrypted aggregated MAC Service Data Unit (A-MSDU) of the first data transmission, wherein the PN=PN.sub.OTA-PN.sub.Offset.

12. The STA of claim 11, wherein the processor is further configured to: transmit, via the transceiver, a block acknowledgement (BA) corresponding to the first data transmission.

13. The STA of claim 11, wherein the processor is further configured to: switch from the first address profile to the second address profile based on the schedule; and receive, via the transceiver, a second data transmission comprising a second RA corresponding to the second address profile,

wherein the first RA and the second RA are different.

14. The STA of claim 11, wherein the processor is further configured to: establish new address profiles with the AP; establish a first time when the new address profiles are available for use; establish a second time when the AP begins operating on a different channel; and transmit on the different channel, via the transceiver, a second data transmission using a third address profile of the new address profiles, after the first and second times.

15. The STA of claim 14, wherein the processor is further configured to: determine an end time for the new address profiles, wherein the third address profile is randomly selected from the new address profiles before the end time.

16. The STA of claim 11, wherein the processor is further configured to: determine a sequence number (SN) using an over-the-air (OTA) sequence number (SN.sub.OTA) of the first data transmission and an offset SN (SN.sub.Offset) of the first address profile, wherein the SN corresponds to the encrypted A-MSDU of the first data transmission.

17. The STA of claim 16, wherein  $SN = SN.sub.OTA - SN.sub.Offset$ .

18. The STA of claim 16, wherein the processor is further configured to: order frames of the first data transmission according to the SN; and decrypt the encrypted A-MSDU.

19. The STA of claim 11, wherein the processor is further configured to: establish a joint algorithm with the AP, wherein the joint algorithm is used to establish the first and the second address profiles as well as transition times for the schedule.

20. A method for an access point (AP), comprising: establishing two or more address profiles with a station (STA); establishing a schedule for switching from a first address profile to a second address profile, wherein the first and second address profiles are of the two or more address profiles; encrypting an aggregated MAC Service Data Unit (A-MSDU); after the encryption, creating an over-the-air (OTA) packet number (PN.sub.OTA) that is different than a packet number (PN) corresponding to the A-MSDU; and transmitting a first data transmission using the first address profile, wherein the first data transmission comprises the PN.sub.OTA, wherein the first address profile comprises an offset PN (PN.sub.Offset), and wherein the  $PN.sub.OTA = PN + PN.sub.Offset$ .

---