

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12402363
Kind Code	B2
Date of Patent	August 26, 2025
Inventor(s)	Yamazaki; Shunpei et al.

Integrated semiconductor with shared electrodes between capacitor and transistor

Abstract

A semiconductor device that can be miniaturized or highly integrated is provided. The semiconductor device includes a first conductor, a second conductor over the first conductor, a first insulator covering the second conductor, a first oxide over the first insulator, and a second oxide over the first oxide, an opening overlapping with at least part of the first conductor is provided in the first oxide and the first insulator, and the second oxide is electrically connected to the first conductor through the opening.

Inventors: Yamazaki; Shunpei (Tokyo, JP), Takeuchi; Toshihiko (Kanagawa, JP), Yamade; Naoto (Kanagawa, JP), Fujiki; Hiroshi (Yamaguchi, JP), Moriwaka; Tomoaki (Kanagawa, JP), Kimura; Shunsuke (Kanagawa, JP)

Applicant: SEMICONDUCTOR ENERGY LABORATORY CO., LTD. (Atsugi, JP)

Family ID: 1000008777707

Assignee: Semiconductor Energy Laboratory Co., Ltd. (Atsugi, JP)

Appl. No.: 18/624488

Filed: April 02, 2024

Prior Publication Data

Document Identifier	Publication Date
US 20240258409 A1	Aug. 01, 2024

Foreign Application Priority Data

JP	2017-047420	Mar. 13, 2017
JP	2017-072177	Mar. 31, 2017

Related U.S. Application Data

continuation parent-doc US 18135793 20230418 US 11955538 child-doc US 18624488
continuation parent-doc US 17176211 20210216 US 11670705 20230606 child-doc US 18135793
continuation parent-doc US 16492282 US 11004961 20210511 WO PCT/IB2018/051253
20180228 child-doc US 17176211

Publication Classification

Int. Cl.: **H01L29/66** (20060101); **H01L21/02** (20060101); **H01L29/10** (20060101); **H01L29/49**
(20060101); **H10B12/00** (20230101); **H10D30/67** (20250101); **H10D30/69** (20250101);
H10D64/66 (20250101)

U.S. Cl.:

CPC **H10D30/751** (20250101); **H01L21/02172** (20130101); **H10B12/30** (20230201);
H10B12/50 (20230201); **H10D30/6729** (20250101); H10D64/667 (20250101)

Field of Classification Search

CPC: H01L (21/02172); H01L (12/30); H01L (12/50); H10D (30/6729)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
5495439	12/1995	Morihara	N/A	N/A
5888854	12/1998	Morihara	N/A	N/A
7576394	12/2008	Furuta et al.	N/A	N/A
7981734	12/2010	Furuta et al.	N/A	N/A
8502216	12/2012	Akimoto et al.	N/A	N/A
8546811	12/2012	Godo et al.	N/A	N/A
8547771	12/2012	Koyama	N/A	N/A
8629437	12/2013	Ishida et al.	N/A	N/A
8709889	12/2013	Saito	N/A	N/A
8835918	12/2013	Yamazaki et al.	N/A	N/A
8865555	12/2013	Yamazaki et al.	N/A	N/A
8907392	12/2013	Yamazaki et al.	N/A	N/A
8946709	12/2014	Kato et al.	N/A	N/A
8975634	12/2014	Yamazaki et al.	N/A	N/A
9029929	12/2014	Saito	N/A	N/A
9048320	12/2014	Yamazaki et al.	N/A	N/A
9082663	12/2014	Isobe et al.	N/A	N/A
9123632	12/2014	Yamazaki et al.	N/A	N/A
9196639	12/2014	Endo	N/A	N/A
9230970	12/2015	Kato et al.	N/A	N/A
9368501	12/2015	Yamazaki et al.	N/A	N/A
9391209	12/2015	Godo et al.	N/A	N/A

9431435	12/2015	Ando et al.	N/A	N/A
9455349	12/2015	Suzawa et al.	N/A	N/A
9466615	12/2015	Miyairi et al.	N/A	N/A
9705006	12/2016	Endo	N/A	N/A
9768318	12/2016	Yamazaki et al.	N/A	N/A
9780201	12/2016	Ando et al.	N/A	N/A
9831309	12/2016	Miyairi	N/A	N/A
9837546	12/2016	Yamazaki et al.	N/A	N/A
9837547	12/2016	Koezuka et al.	N/A	N/A
9865712	12/2017	Okamoto et al.	N/A	N/A
9887295	12/2017	Suzawa et al.	N/A	N/A
10062790	12/2017	Yamazaki et al.	N/A	N/A
10069014	12/2017	Yamazaki et al.	N/A	N/A
10103271	12/2017	Suzawa et al.	N/A	N/A
10158005	12/2017	Akimoto et al.	N/A	N/A
10186604	12/2018	Ando et al.	N/A	N/A
10199508	12/2018	Yamazaki et al.	N/A	N/A
10204898	12/2018	Momo et al.	N/A	N/A
10229904	12/2018	Yamazaki et al.	N/A	N/A
10236287	12/2018	Yamazaki	N/A	N/A
10319861	12/2018	Koezuka et al.	N/A	N/A
10446671	12/2018	Okamoto et al.	N/A	N/A
10522691	12/2018	Yamazaki et al.	N/A	N/A
10756080	12/2019	Yamazaki et al.	N/A	N/A
10861981	12/2019	Koezuka et al.	N/A	N/A
10879381	12/2019	Okamoto et al.	N/A	N/A
10903368	12/2020	Koezuka et al.	N/A	N/A
11538940	12/2021	Yamazaki et al.	N/A	N/A
11670705	12/2022	Yamazaki	257/43	H01L 21/28
2010/0065839	12/2009	Yamazaki et al.	N/A	N/A
2010/0224878	12/2009	Kimura	N/A	N/A
2011/0233536	12/2010	Kim et al.	N/A	N/A
2012/0068179	12/2011	Ishida. et al.	N/A	N/A
2012/0187396	12/2011	Yamazaki et al.	N/A	N/A
2013/0069053	12/2012	Yamazaki et al.	N/A	N/A
2013/0075722	12/2012	Yamazaki et al.	N/A	N/A
2013/0140569	12/2012	Yoneda et al.	N/A	N/A
2013/0153893	12/2012	Morosawa et al.	N/A	N/A
2013/0299824	12/2012	Akimoto et al.	N/A	N/A
2014/0034954	12/2013	Yamazaki et al.	N/A	N/A
2014/0042432	12/2013	Yamazaki	N/A	N/A
2014/0061636	12/2013	Miyake et al.	N/A	N/A
2014/0061654	12/2013	Yamazaki et al.	N/A	N/A
2014/0070209	12/2013	Yamazaki et al.	N/A	N/A
2014/0077208	12/2013	Matsukura	N/A	N/A
2014/0167133	12/2013	Hirano et al.	N/A	N/A
2014/0175433	12/2013	Yamazaki et al.	N/A	N/A
2014/0175436	12/2013	Yamazaki	N/A	N/A
2014/0183523	12/2013	Endo	N/A	N/A
2014/0183528	12/2013	Endo	N/A	N/A

2014/0209897	12/2013	Kubota et al.	N/A	N/A
2014/0241487	12/2013	Yamazaki et al.	N/A	N/A
2014/0299874	12/2013	Yamazaki	N/A	N/A
2014/0306219	12/2013	Yamazaki et al.	N/A	N/A
2014/0312342	12/2013	Yamazaki	N/A	N/A
2014/0339539	12/2013	Yamazaki et al.	N/A	N/A
2014/0339546	12/2013	Yamazaki et al.	N/A	N/A
2014/0362317	12/2013	Kubota et al.	N/A	N/A
2014/0362324	12/2013	Yamazaki et al.	N/A	N/A
2015/0014681	12/2014	Yamazaki	N/A	N/A
2015/0053969	12/2014	Ito et al.	N/A	N/A
2015/0076492	12/2014	Kubota et al.	N/A	N/A
2015/0084047	12/2014	Yamazaki	N/A	N/A
2015/0108472	12/2014	Suzawa et al.	N/A	N/A
2015/0108474	12/2014	Yamazaki et al.	N/A	N/A
2015/0108475	12/2014	Ando et al.	N/A	N/A
2015/0187814	12/2014	Miyairi et al.	N/A	N/A
2015/0255518	12/2014	Watanabe et al.	N/A	N/A
2015/0270288	12/2014	Yamazaki et al.	N/A	N/A
2015/0346548	12/2014	Kubota	N/A	N/A
2015/0349132	12/2014	Yamazaki	N/A	N/A
2016/0043070	12/2015	Momo et al.	N/A	N/A
2016/0155849	12/2015	Noda	N/A	N/A
2016/0190331	12/2015	Miyake et al.	N/A	N/A
2016/0233343	12/2015	Miyairi	N/A	N/A
2016/0274394	12/2015	Yamazaki et al.	N/A	N/A
2016/0293605	12/2015	Yamazaki et al.	N/A	N/A
2016/0322388	12/2015	Ma et al.	N/A	N/A
2016/0322395	12/2015	Koezuka et al.	N/A	N/A
2016/0328080	12/2015	Miyake	N/A	N/A
2016/0343868	12/2015	Koezuka et al.	N/A	N/A
2017/0012138	12/2016	Suzawa et al.	N/A	N/A
2017/0019972	12/2016	Kimura et al.	N/A	N/A
2017/0110337	12/2016	Akimoto et al.	N/A	N/A
2017/0168333	12/2016	Kubota et al.	N/A	N/A
2018/0204884	12/2017	Isa	N/A	N/A
2019/0157262	12/2018	Momo et al.	N/A	N/A
2020/0052099	12/2019	Yamazaki et al.	N/A	N/A
2020/0350308	12/2019	Yamazaki et al.	N/A	N/A
2021/0074834	12/2020	Okamoto et al.	N/A	N/A
2021/0119056	12/2020	Koezuka et al.	N/A	N/A
2023/0093689	12/2022	Yamazaki et al.	N/A	N/A
2024/0113230	12/2023	Yamazaki et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101326644	12/2007	CN	N/A
102210025	12/2010	CN	N/A
104810375	12/2014	CN	N/A
105590964	12/2015	CN	N/A

105659369	12/2015	CN	N/A
07-142607	12/1994	JP	N/A
2011-205054	12/2010	JP	N/A
2011-210744	12/2010	JP	N/A
2011-216879	12/2010	JP	N/A
2012-256877	12/2011	JP	N/A
2012-257187	12/2011	JP	N/A
2013-093561	12/2012	JP	N/A
2013-149970	12/2012	JP	N/A
2014-199416	12/2013	JP	N/A
2015-084417	12/2014	JP	N/A
2015-109425	12/2014	JP	N/A
2015-109429	12/2014	JP	N/A
2015-144271	12/2014	JP	N/A
2016-039375	12/2015	JP	N/A
2016-149552	12/2015	JP	N/A
2016-154225	12/2015	JP	N/A
2016-167584	12/2015	JP	N/A
2016-189464	12/2015	JP	N/A
2016-192571	12/2015	JP	N/A
2017-028252	12/2016	JP	N/A
2013-0035744	12/2012	KR	N/A
2013-0136888	12/2012	KR	N/A
2016-0073374	12/2015	KR	N/A
2016-0102295	12/2015	KR	N/A
201222733	12/2011	TW	N/A
201523885	12/2014	TW	N/A
201532248	12/2014	TW	N/A
WO-2007/089048	12/2006	WO	N/A
WO-2010/032638	12/2009	WO	N/A
WO-2010/053060	12/2009	WO	N/A
WO-2011/096275	12/2010	WO	N/A
WO-2011/114919	12/2010	WO	N/A
WO-2015/060318	12/2014	WO	N/A
WO-2015/097589	12/2014	WO	N/A
WO-2016/128859	12/2015	WO	N/A
WO-2016/139548	12/2015	WO	N/A
WO-2016/189411	12/2015	WO	N/A

OTHER PUBLICATIONS

International Search Report (Application No. PCT/IB2018/051253) Dated May 15, 2018. cited by applicant

Written Opinion (Application No. PCT/IB2018/051253) Dated May 15, 2018. cited by applicant
Yamazaki.S et al., “Research, Development, and Application of Crystalline Oxide Semiconductor”,
SID Digest '12 : SID International Symposium Digest of Technical Papers, Jun. 5, 2012, vol. 43,
No. 1, pp. 183-186. cited by applicant

Yamazaki.S et al., “Properties of crystalline In—Ga—Zn-oxide semiconductor and its transistor characteristics”, Jpn. J. Appl. Phys. (Japanese Journal of Applied Physics) , Mar. 31, 2014, vol. 53,
No. 4S, pp. 04ED18-1-04ED18-10, The Japan Society of Applied Physics. cited by applicant
Ito.S et al., “Analysis of Nanoscale Crystalline Structure of In—Ga—Zn—O Thin Film with Nano

Beam Electron Diffraction”, AM-FPD '13 Digest of Technical Papers, Jul. 2, 2013, pp. 151-154. cited by applicant

Yamazaki.S et al., “In—Ga—Zn-Oxide Semiconductor and Its Transistor Characteristics”, ECS Journal of Solid State Science and Technology, Jul. 1, 2014, vol. 3, No. 9, pp. Q3012-Q3022. cited by applicant

Yamazaki.S, “Crystalline Oxide Semiconductor Using CAAC-IGZO and its Application”, ECS Transactions, Oct. 1, 2014, vol. 64, No. 10, pp. 155-164, The Electrochemical Society. cited by applicant

Kato.K et al., “Evaluation of Off-State Current Characteristics of Transistor Using Oxide Semiconductor Material, Indium-Gallium-Zinc Oxide”, Jpn. J. Appl. Phys. (Japanese Journal of Applied Physics) , 2012, vol. 51, pp. 021201-1-021201-7, The Japan Society of Applied Physics. cited by applicant

Matsuda.S et al., “30-nm-Channel-Length C-Axis Aligned Crystalline In—Ga—Zn—O Transistors with Low Off-State Leakage Current and Steep Subthreshold Characteristics”, 2015 Symposium on VLSI Technology : Digest of Technical Papers, 2015, pp. T216-T217. cited by applicant

Amano.S et al., “Low Power LC Display Using In—Ga—Zn—Oxide TFTs Based on Variable Frame Frequency”, SID Digest '10 : SID International Symposium Digest of Technical Papers, May 23, 2010, vol. 41, No. 1, pp. 626-629. cited by applicant

Indian Office Action (Application No. 201917037507) Dated Feb. 1, 2022. cited by applicant

German Office Action (Application No. 112018001295.6) Dated Dec. 15, 2022. cited by applicant

Zhang.X et al., “Research Progress On Oxide based Thin Film Transistors”, Advanced Display, Apr. 15, 2009, vol. 20, No. 4, pp. 28-33. cited by applicant

Chinese Office Action (Application No. 201880016444.0) Dated Mar. 30, 2023. cited by applicant

Primary Examiner: Monbleau; Davienne N

Assistant Examiner: Grewal; Heim Kirin

Attorney, Agent or Firm: Fish & Richardson P.C.

Background/Summary

CROSS REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. application Ser. No. 18/135,793, filed Apr. 18, 2023, now allowed, which is incorporated by reference and is a continuation of U.S. application Ser. No. 17/176,211, filed Feb. 16, 2021, now U.S. Pat. No. 11,670,705, which is incorporated by reference and is a continuation of U.S. application Ser. No. 16/492,282, filed Sep. 9, 2019, now U.S. Pat. No. 11,004,961, which claims the benefit of a U.S. National Phase Application under 35 U.S.C. § 371 of International Application PCT/IB2018/051253, filed on Feb. 28, 2018, which is incorporated by reference and claims the benefit of two foreign priority applications filed in Japan as Application No. 2017-047420 on Mar. 13, 2017, and as 2017-072177 and Mar. 31, 2017.

TECHNICAL FIELD

(1) One embodiment of the present invention relates to a semiconductor device and a manufacturing method of a semiconductor device. One embodiment of the present invention relates to a semiconductor wafer, a module, and an electronic device.

(2) Note that in this specification and the like, a semiconductor device generally means a device that can function by utilizing semiconductor characteristics. A semiconductor element such as a transistor, a semiconductor circuit, an arithmetic device, and a memory device are each an

embodiment of a semiconductor device. In some cases, it can be said that a display device (a liquid crystal display device, a light-emitting display device, and the like), a projection device, a lighting device, an electro-optical device, a power storage device, a memory device, a semiconductor circuit, an imaging device, an electronic device, and the like each include a semiconductor device. (3) Note that one embodiment of the present invention is not limited to the above technical field. One embodiment of the invention disclosed in this specification and the like relates to an object, a method, or a manufacturing method. One embodiment of the present invention relates to a process, a machine, manufacture, or a composition of matter.

BACKGROUND ART

(4) Integrated circuits (IC) using semiconductor elements have been developed. A CPU and a memory have been developed and manufactured with technology for an LSI including a highly integrated IC or an ultra LSI. Such an IC is mounted on a circuit board, for example, a printed wiring board, to be used as one of components of a variety of electronic devices included in a computer, an information terminal, a display device, an automobile, and the like. Moreover, utilization of these ICs for an artificial intelligence (AI) system has been studied.

(5) As computers and information terminals, desktop computers, laptop computers, tablet computers, smartphones, cell phones, and the like are known.

(6) A silicon-based semiconductor material is widely known as a semiconductor material used for a semiconductor element; in addition, an oxide semiconductor has attracted attention as another material.

(7) Moreover, it is known that a transistor including an oxide semiconductor has an extremely low leakage current in a non-conduction state. For example, a low-power consumption CPU utilizing a characteristic of low leakage current of the transistor including an oxide semiconductor has been disclosed (see Patent Document 1).

(8) Furthermore, in recent years, demand for an integrated circuit with higher density has risen with reductions in the size and weight of electronic devices. In addition, the productivity of semiconductor devices including an integrated circuit is required to be improved.

(9) Here, not only single-component metal oxides, such as indium oxide and zinc oxide, but also multi-component metal oxides are known as an oxide semiconductor. Among the multi-component metal oxides, in particular, an In—Ga—Zn oxide (hereinafter also referred to as IGZO) has been actively studied.

(10) From the studies on IGZO, in the oxide semiconductor, a CAAC (c-axis aligned crystalline) structure and an nc (nanocrystalline) structure, which are not single crystal nor amorphous, have been found (see Non-Patent Document 1 to Non-Patent Document 3). Non-Patent Document 1 and Non-Patent Document 2 disclose a technique for forming a transistor by using an oxide semiconductor having a CAAC structure. Moreover, Non-Patent Document 4 and Non-Patent Document 5 disclose that even an oxide semiconductor which has lower crystallinity than those of the CAAC structure and the nc structure includes a minute crystal.

(11) In addition, a transistor which includes IGZO as an active layer has an extremely low off-state current (see Non-Patent Document 6), and an LSI and a display utilizing the characteristic have been reported (see Non-Patent Document 7 and Non-Patent Document 8).

REFERENCES

Patent Documents

(12) [Patent Document 1] Japanese Published Patent Application No. 2012-257187

Non-Patent Documents

(13) [Non-Patent Document 1] S. Yamazaki et al., “SID Symposium Digest of Technical Papers”, 2012, volume 43, issue 1, pp. 183-186 [Non-Patent Document 2] S. Yamazaki et al., “Japanese Journal of Applied Physics”, 2014, volume 53, Number 4S, pp. 04ED18-1-04ED18-10 [Non-Patent Document 3] S. Ito et al., “The Proceedings of AM-FPD'13 Digest of Technical Papers”, 2013, pp. 151-154 [Non-Patent Document 4] S. Yamazaki et al., “ECS Journal of Solid State Science and

Technology”, 2014, volume 3, issue 9, pp. Q3012-Q3022 [Non-Patent Document 5] S. Yamazaki, “ECS Transactions”, 2014, volume 64, issue 10, pp. 155-164 [Non-Patent Document 6] K. Kato et al., “Japanese Journal of Applied Physics”, 2012, volume 51, pp. 021201-1-021201-7 [Non-Patent Document 7] S. Matsuda et al., “2015 Symposium on VLSI Technology Digest of Technical Papers”, 2015, pp. T216-T217 [Non-Patent Document 8] S. Amano et al., “SID Symposium Digest of Technical Papers”, 2010, volume 41, issue 1, pp. 626-629

SUMMARY OF THE INVENTION

Problems to be Solved by the Invention

(14) One object of one embodiment of the present invention is to provide a semiconductor device with favorable electrical characteristics and a manufacturing method thereof. One object of one embodiment of the present invention is to provide a highly reliable semiconductor device and a manufacturing method thereof. One object of one embodiment of the present invention is to provide a semiconductor device that can be miniaturized or highly integrated and a manufacturing method thereof. One object of one embodiment of the present invention is to provide a semiconductor device with high productivity and a manufacturing method thereof.

(15) One object of one embodiment of the present invention is to provide a semiconductor device that has suppressed variation in electrical characteristics, stable electrical characteristics, and improved reliability. Another object of one embodiment of the present invention is to provide a semiconductor device capable of retaining data for a long time. Another object of one embodiment of the present invention is to provide a semiconductor device capable of high-speed data writing. Another object of one embodiment of the present invention is to provide a novel semiconductor device.

(16) One object of one embodiment of the present invention is to provide a semiconductor device with high design flexibility. Another object of one embodiment of the present invention is to provide a semiconductor device with reduced power consumption.

(17) One object of one embodiment of the present invention is to provide a semiconductor device whose manufacturing process is simplified and a manufacturing method thereof. Another object of one embodiment of the present invention is to provide a semiconductor device with reduced area and a manufacturing method thereof.

(18) Note that the descriptions of these objects do not disturb the existence of other objects. Note that one embodiment of the present invention does not have to solve all of these objects. Note that objects other than these objects will be apparent and can be derived from the descriptions of the specification, the drawings, the claims, and the like.

Means for Solving the Problems

(19) One embodiment of the present invention is a semiconductor device including a first conductor; a second conductor over the first conductor; a first insulator covering the second conductor; a first oxide over the first insulator; and a second oxide over the first oxide. An opening overlapping with at least part of the first conductor is provided in the first oxide and the first insulator, and the second oxide is electrically connected to the first conductor through the opening.

(20) In the above, an end portion of the second oxide is preferably substantially aligned with an end portion of the first oxide.

(21) In the above, the semiconductor device may further include a third conductor; a fourth conductor over the third conductor; a third oxide over the second oxide; a second insulator over the third oxide; and a fifth conductor over the second insulator, and it is preferable that the fourth conductor be covered with the first insulator, and the fifth conductor overlap with the third conductor and the fourth conductor with the first insulator, the first oxide, the second oxide, the third oxide, and the second insulator interposed therebetween.

(22) In the above, the first conductor and the third conductor preferably contain the same material and the second conductor and the fourth conductor preferably contain the same material.

(23) In the above, the second conductor preferably includes a metal nitride.

(24) In the above, the metal nitride is preferably titanium nitride or tantalum nitride.

(25) One embodiment of the present invention is a method for manufacturing a semiconductor device in which a first conductive film is formed over an insulating surface; a second conductive film is formed over the first conductive film; the second conductive film and the first conductive film are patterned to form a first conductor and a second conductor over the first conductor; a first insulating film is formed to cover the first conductor and the second conductor; the first insulating film is processed to expose the second conductor so that the first insulator is formed; a second insulator is formed over the first insulator and the second conductor; a first oxide film is formed over the second insulator; an opening overlapping with at least part of the first conductor is formed in the first oxide film and the second insulator; a second oxide film is formed over the first oxide film; the second oxide film and the first oxide film are patterned to form a first oxide and a second oxide over the first oxide; and the second oxide is electrically connected to the first conductor through the opening.

(26) In the above, the second conductive film and the first conductive film may be patterned to further form a third conductor and a fourth conductor over the third conductor; a third oxide film may be formed over the second oxide; a second insulating film may be formed over the third oxide film; a third conductive film may be formed over the second insulating film; the third conductive film may be patterned to form a fifth conductor; the second insulating film may be patterned to form a third insulator; and the third oxide film may be patterned to form a third oxide, and it is preferable that the fifth conductor overlap with the third conductor and the fourth conductor with the second insulator, the first oxide, the second oxide, the third oxide, and the third insulator interposed therebetween.

(27) In the above, the second conductive film preferably includes a metal nitride.

(28) In the above, the metal nitride is preferably titanium nitride or tantalum nitride.

(29) One embodiment of the present invention is a semiconductor device including a first conductor; a first insulator over the first conductor; a first oxide over the first insulator; a second oxide over the first oxide; a third oxide over the second oxide; a second insulator over the third oxide; a second conductor over the second insulator; a third insulator provided on a side surface of the second insulator and a side surface of the second conductor; and a fourth insulator provided on a side surface of the third insulator, an opening overlapping with part of the first conductor is provided in the first oxide and the first insulator, and the second oxide is electrically connected to the first conductor through the opening.

(30) In the above, a side surface of the second oxide and a side surface of the third oxide are preferably on the same plane as a side surface of the first oxide.

(31) In the above, an end portion of the second oxide and an end portion of the third oxide are preferably substantially aligned with an end portion of the first oxide.

(32) In the above, the semiconductor device may further include a third conductor and a fourth oxide, and it is preferable that the fourth oxide be provided between the third oxide and the second insulator, and the third conductor overlap with the second conductor with the first insulator, the first oxide, the second oxide, the third oxide, the fourth oxide, and the second insulator interposed therebetween.

(33) In the above, the first conductor and the third conductor preferably include the same material.

(34) One embodiment of the present invention is a method for manufacturing a semiconductor device in which a first insulating film is formed over a first conductor and a second conductor; a first oxide film is formed over the first insulating film; an opening overlapping with at least part of the first conductor is formed in the first oxide film and the first insulating film; a second oxide film is formed over the first oxide film and the first conductor; a third oxide film is formed over the second oxide film; the third oxide film, the second oxide film, and the first oxide film are patterned to form a first oxide, a second oxide over the first oxide, and a third oxide over the second oxide; a second insulating film is formed to cover the first oxide, the second oxide, and the third oxide; a

first conductive film is formed over the second insulating film; the first conductive film and the second insulating film are patterned to form a third conductor and a first insulator; a third insulating film is formed to cover the third conductor and the first insulator; a fourth insulating film is formed over the third insulating film; and the fourth insulating film and the third insulating film are processed by etching to form a second insulator on a side surface of the third conductor and a side surface of the first insulator, and a third insulator on a side surface of the second insulator.

(35) In the above, the third conductor preferably overlaps with the second conductor with the first insulating film, the first oxide, the second oxide, the third oxide, and the first insulator interposed therebetween.

Effect of the Invention

(36) According to one object of one embodiment of the present invention, a semiconductor device with favorable electrical characteristics and a manufacturing method thereof can be provided.

According to one object of one embodiment of the present invention, a highly reliable semiconductor device and a manufacturing method thereof can be provided. According to one embodiment of the present invention, a semiconductor device that can be miniaturized or highly integrated and a manufacturing method thereof can be provided. According to one embodiment of the present invention, a semiconductor device with high productivity and a manufacturing method thereof can be provided.

(37) According to one embodiment of the present invention, a semiconductor device that has suppressed variation in electrical characteristics, stable electrical characteristics, and improved reliability can be provided. A semiconductor device capable of retaining data for a long time can be provided. A semiconductor device capable of high-speed data writing can be provided. A novel semiconductor device can be provided.

(38) According to one embodiment of the present invention, a semiconductor device with high design flexibility can be provided. A semiconductor device with reduced power consumption can be provided.

(39) According to one embodiment of the present invention, a semiconductor device whose manufacturing process is simplified and a manufacturing method thereof can be provided.

(40) According to one embodiment of the present invention, a semiconductor device with reduced area and a manufacturing method thereof can be provided.

(41) Note that the descriptions of these effects do not disturb the existence of other effects. Note that one embodiment of the present invention does not have to have all of these effects. Note that effects other than these effects will be apparent and can be derived from the descriptions of the specification, the drawings, the claims, and the like.

Description

BRIEF DESCRIPTION OF DRAWINGS

(1) FIGS. 1A-1D A top view and cross-sectional views illustrating a semiconductor device of one embodiment of the present invention.

(2) FIG. 2 A cross-sectional view illustrating a semiconductor device of one embodiment of the present invention.

(3) FIGS. 3A-3D A top view and cross-sectional views illustrating a semiconductor device of one embodiment of the present invention.

(4) FIGS. 4A-4D A top view and cross-sectional views illustrating a semiconductor device of one embodiment of the present invention.

(5) FIGS. 5A-5D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(6) FIGS. 6A-6D A top view and cross-sectional views illustrating a method for manufacturing a

semiconductor device of one embodiment of the present invention.

(7) FIGS. 7A-7D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(8) FIGS. 8A-8D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(9) FIGS. 9A-9D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(10) FIGS. 10A-10D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(11) FIGS. 11A-11D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(12) FIGS. 12A-12D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(13) FIGS. 13A-13D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(14) FIGS. 14A-14D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(15) FIGS. 15A-15D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(16) FIGS. 16A-16D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(17) FIGS. 17A-17D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(18) FIGS. 18A-18D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(19) FIGS. 19A-19D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(20) FIGS. 20A-20D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(21) FIGS. 21A-21D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(22) FIGS. 22A-22D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(23) FIGS. 23A-23D A top view and cross-sectional views of a semiconductor device of one embodiment of the present invention.

(24) FIG. 24 A cross-sectional view of a semiconductor device of one embodiment of the present invention.

(25) FIGS. 25A-25D A top view and cross-sectional views of a semiconductor device of one embodiment of the present invention.

(26) FIGS. 26A-26D A top view and cross-sectional views of a semiconductor device of one embodiment of the present invention.

(27) FIG. 27 A circuit diagram of a semiconductor device of one embodiment of the present invention.

(28) FIGS. 28A and 28B A circuit diagram and a cross-sectional view of a semiconductor device of one embodiment of the present invention.

(29) FIG. 29 A cross-sectional view of a semiconductor device of one embodiment of the present invention.

(30) FIGS. 30A-30D A top view and cross-sectional views illustrating a method for manufacturing a semiconductor device of one embodiment of the present invention.

(31) FIGS. 31A-31D A top view and cross-sectional views illustrating a method for manufacturing

the present invention.

(57) FIG. 57 A block diagram illustrating a structure example of a memory device of one embodiment of the present invention.

(58) FIGS. 58A-58E Circuit diagrams illustrating configuration examples of memory devices of embodiments of the present invention.

(59) FIG. 59 A circuit diagram showing a configuration example of a memory device of one embodiment of the present invention.

(60) FIG. 60 A cross-sectional view illustrating a structure of a memory device of one embodiment of the present invention.

(61) FIG. 61 A block diagram illustrating a configuration example of a memory device of one embodiment of the present invention.

(62) FIGS. 62A and 62B A block diagram and a circuit diagram showing a configuration example of a memory device of one embodiment of the present invention.

(63) FIGS. 63A-63C Block diagrams illustrating a structure example of a semiconductor device of one embodiment of the present invention.

(64) FIGS. 64A-64C A block diagram and a circuit diagram showing a configuration example of a semiconductor device of one embodiment of the present invention, and a timing chart illustrating an operation example of the semiconductor device.

(65) FIG. 65 A block diagram illustrating a structure example of a semiconductor device of one embodiment of the present invention.

(66) FIGS. 66A and 66B A circuit diagram showing a configuration example of a semiconductor device of one embodiment of the present invention, and a timing chart illustrating an operation example of the semiconductor device.

(67) FIG. 67 A block diagram illustrating a structure example of an AI system of one embodiment of the present invention.

(68) FIGS. 68A and 68B Block diagrams illustrating application examples of an AI system of embodiments of the present invention.

(69) FIG. 69 A schematic perspective view illustrating a structure example of an IC incorporating an AI system of one embodiment of the present invention.

(70) FIGS. 70A-70F Diagrams illustrating electronic devices of embodiments of the present invention.

MODE FOR CARRYING OUT THE INVENTION

(71) Hereinafter, embodiments will be described with reference to drawings. Note that the embodiments can be implemented with various modes, and it will be readily appreciated by those skilled in the art that modes and details can be changed in various ways without departing from the spirit and scope. Thus, the present invention should not be interpreted as being limited to the following description of the embodiments.

(72) In the drawings, the size, the layer thickness, or the region is exaggerated for clarity in some cases. Therefore, they are not limited to the scale. Note that the drawings are schematic views showing ideal examples, and shapes, values or the like are not limited to shapes, values or the like shown in the drawings. For example, in the actual manufacturing process, a layer or a resist mask might be unintentionally reduced in size by treatment such as etching, which is omitted in some cases for easy understanding. In the drawings, the same portions or portions having similar functions are denoted by the same reference numerals in different drawings, and explanation thereof is not repeated in some cases. Furthermore, the same hatching pattern is applied to portions having similar functions, and the portions are not particularly denoted by reference numerals in some cases.

(73) Furthermore, particularly in a top view (also referred to as a “plan view”), a perspective view, or the like, illustration of some components might be omitted for easy understanding of the invention. In addition, illustration of some hidden lines and the like might be omitted.

(74) The ordinal numbers such as first and second in this specification and the like are used for convenience and do not denote the order of steps or the stacking order of layers. Therefore, for example, “first” can be replaced with “second” or “third” as appropriate for description. In addition, the ordinal numbers in this specification and the like do not correspond to the ordinal numbers that are used to specify one embodiment of the present invention in some cases.

(75) In this specification, terms for describing arrangement, such as “over” and “under”, are used for convenience to describe a positional relation between components with reference to drawings. Furthermore, the positional relation between components is changed as appropriate in accordance with a direction in which each component is illustrated. Thus, there is no limitation on terms described in this specification, and the terms can be changed appropriately depending on the situation.

(76) In the case where there is an explicit description X and Y are connected in this specification and the like, for example, the case where X and Y are electrically connected, the case where X and Y are functionally connected, and the case where X and Y are directly connected are disclosed in this specification and the like. Accordingly, without being limited to a predetermined connection relation, for example, a connection relation shown in drawings or texts, a connection relation other than one shown in drawings or texts is included in the drawings or the texts.

(77) Here, X and Y each denote an object (for example, a device, an element, a circuit, a wiring, an electrode, a terminal, a conductive film, or a layer).

(78) An example of the case where X and Y are directly connected as follows: an element that allows an electrical connection between X and Y (for example, a switch, a transistor, a capacitor, an inductor, a resistor, a diode, a display element, a light-emitting element, or a load) is not connected between X and Y, or the case where X and Y are connected without the element that allows the electrical connection between X and Y (for example, a switch, a transistor, a capacitor, an inductor, a resistor, a diode, a display element, a light-emitting element, or a load) provided therebetween.

(79) An example of the case where X and Y are electrically connected as follows: one or more elements that allow an electrical connection between X and Y (for example, a switch, a transistor, a capacitor, an inductor, a resistor, a diode, a display element, a light-emitting element, or a load) can be connected between X and Y. Note that the switch has a function of being controlled to be turned on or off. That is, the switch has a function of being in a conduction state (on state) or a non-conduction state (off state) to control a path where current flows. The switch has a function of selecting and changing a current path. Note that the case where X and Y are electrically connected includes the case where X and Y are directly connected.

(80) An example of the case where X and Y are functionally connected as follows: one or more circuits that allow a functional connection between X and Y (for example, a logic circuit (an inverter, a NAND circuit, a NOR circuit, or the like), a signal converter circuit (a DA converter circuit, an AD converter circuit, a gamma correction circuit, or the like), a potential level converter circuit (a power supply circuit (a step-up circuit, a step-down circuit, or the like), a level shifter circuit for changing the potential level of a signal, or the like), a voltage source, a current source, a switching circuit, an amplifier circuit (a circuit that can increase signal amplitude, the amount of current, or the like, an operational amplifier, a differential amplifier circuit, a source follower circuit, a buffer circuit, or the like), a signal generation circuit, a memory circuit, or a control circuit) can be connected between X and Y. Note that, for example, when another circuit is interposed between X and Y and a signal output from X is transmitted to Y, X and Y are regarded as being functionally connected. Note that the case where X and Y are functionally connected includes the case where X and Y are directly connected and the case where X and Y are electrically connected.

(81) In this specification and the like, a transistor is an element having at least three terminals including a gate, a drain, and a source. The transistor has a channel formation region between the drain (a drain terminal, a drain region, or a drain electrode) and the source (a source terminal, a

source region, or a source electrode), and current can flow between the source and the drain through the channel formation region. Note that in this specification and the like, a channel formation region refers to a region through which current mainly flows.

(82) Furthermore, functions of a source and a drain might be switched when a transistor of opposite polarity is employed or the direction of current flow is changed in circuit operation, for example. Therefore, the terms “source” and “drain” can be switched in some cases in this specification and the like.

(83) Note that a channel length refers to, for example, the distance between a source (a source region or a source electrode) and a drain (a drain region or a drain electrode) in a region where a semiconductor (or a portion where current flows in a semiconductor when a transistor is on) and a gate electrode overlap with each other or a region where a channel is formed in a top view of the transistor. Note that in one transistor, channel lengths in all regions are not necessarily the same. In other words, the channel length of one transistor is not fixed to one value in some cases. Thus, in this specification, the channel length is any one of values, the maximum value, the minimum value, or the average value in a region where a channel is formed.

(84) The channel width refers to, for example, the length of a portion where a source and a drain face each other in a region where a semiconductor (or a portion where current flows in a semiconductor when a transistor is on) and a gate electrode overlap with each other, or a region where a channel is formed in a top view of the transistor. Note that in one transistor, channel widths in all regions are not necessarily the same. In other words, the channel width of one transistor is not fixed to one value in some cases. Thus, in this specification, the channel width is any one of values, the maximum value, the minimum value, or the average value in a region where a channel is formed.

(85) Note that depending on transistor structures, a channel width in a region where a channel is actually formed (hereinafter also referred to as an “effective channel width”) is different from a channel width shown in a top view of a transistor (hereinafter also referred to as an “apparent channel width”) in some cases. For example, in the case where a gate electrode covers a side surface of a semiconductor, an effective channel width is larger than an apparent channel width, and its influence cannot be ignored in some cases. For example, in a miniaturized transistor having a gate electrode covering a side surface of a semiconductor, the proportion of a channel formation region formed in the side surface of the semiconductor is increased in some cases. In that case, an effective channel width is larger than an apparent channel width.

(86) In such a case, an effective channel width might be difficult to estimate by actual measurement. For example, estimation of an effective channel width from a design value requires an assumption that the shape of a semiconductor is known. Accordingly, in the case where the accurate shape of a semiconductor is not known, it is difficult to measure an effective channel width accurately.

(87) Thus, in this specification, an apparent channel width is referred to as a “surrounded channel width (SCW)” in some cases. Furthermore, in this specification, the simple term “channel width” refers to a surrounded channel width or an apparent channel width in some cases. Alternatively, in this specification, the simple term “channel width” refers to an effective channel width in some cases. Note that a channel length, a channel width, an effective channel width, an apparent channel width, a surrounded channel width, and the like can be determined by, for example, analyzing a cross-sectional TEM image.

(88) Note that an impurity in a semiconductor refers to, for example, an element other than the main components of the semiconductor. For example, an element with a concentration lower than 0.1 atomic % can be regarded as an impurity. When an impurity is contained, for example, the DOS (Density of States) in a semiconductor may be increased, or the crystallinity may be decreased. In the case where the semiconductor is an oxide semiconductor, examples of an impurity which changes the characteristics of the semiconductor include Group 1 elements, Group 2 elements,

Group 13 elements, Group 14 elements, Group 15 elements, and transition metals other than the main components of the oxide semiconductor; hydrogen, lithium, sodium, silicon, boron, phosphorus, carbon, and nitrogen are given as examples. In the case of an oxide semiconductor, water also functions as an impurity in some cases. In addition, in the case of an oxide semiconductor, entry of impurities may form oxygen vacancies, for example. When the semiconductor is silicon, examples of an impurity which changes the characteristics of the semiconductor include oxygen, Group 1 elements except hydrogen, Group 2 elements, Group 13 elements, and Group 15 elements.

(89) Note that in this specification and the like, a silicon oxynitride film contains more oxygen than nitrogen in its composition. A silicon oxynitride film preferably contains, for example, oxygen in the range of 55 atomic % to 65 atomic %, nitrogen in the range of 1 atomic % to 20 atomic %, silicon in the range of 25 atomic % to 35 atomic %, and hydrogen in the range of 0.1 atomic % to 10 atomic %. A silicon nitride oxide film contains more nitrogen than oxygen in its composition. A silicon nitride oxide film preferably contains nitrogen in the range of 55 atomic % to 65 atomic %, oxygen in the range of 1 atomic % to 20 atomic %, silicon in the range of 25 atomic % to 35 atomic %, and hydrogen in the range of 0.1 atomic % to 10 atomic %, for example.

(90) In this specification and the like, the term “film” and the term “layer” can be interchanged with each other. For example, the term “conductive layer” can be changed into the term “conductive film” in some cases. For another example, the term “insulating film” can be changed into the term “insulating layer” in some cases.

(91) In addition, in this specification and the like, the term “insulator” can be replaced with “insulating film” or “insulating layer”. Moreover, the term “conductor” can be replaced with “conductive film” or “conductive layer”. Furthermore, the term “semiconductor” can be replaced with “semiconductor film” or “semiconductor layer”.

(92) Furthermore, unless otherwise specified, transistors described in this specification and the like are field effect transistors. Unless otherwise specified, transistors described in this specification and the like are n-channel transistors. Thus, unless otherwise specified, the threshold voltage (also referred to as “ V_{th} ”) is higher than 0 V.

(93) In this specification and the like, “parallel” refers to a state where two straight lines are arranged such that the angle formed therebetween is greater than or equal to -10° and less than or equal to 10° . Accordingly, the case where the angle is greater than or equal to -5° and less than or equal to 5° is also included. In addition, “substantially parallel” indicates a state where two straight lines are arranged such that the angle formed therebetween is greater than or equal to -30° and less than or equal to 30° . Moreover, “perpendicular” indicates a state where two straight lines are arranged such that the angle formed therebetween is greater than or equal to 80° and less than or equal to 100° . Accordingly, the case where the angle is greater than or equal to 85° and less than or equal to 95° is also included. In addition, “substantially perpendicular” indicates a state where two straight lines are arranged such that the angle formed therebetween is greater than or equal to 60° and less than or equal to 120° .

(94) In this specification, trigonal and rhombohedral crystal systems are included in a hexagonal crystal system.

(95) Note that in this specification, a barrier film refers to a film having a function of inhibiting passage of oxygen and impurities such as hydrogen, and in the case where the barrier film has conductivity, it may be referred to as a conductive barrier film.

(96) In this specification and the like, a metal oxide means an oxide of metal in a broad expression. Metal oxides are classified into an oxide insulator, an oxide conductor (including a transparent oxide conductor), an oxide semiconductor (also simply referred to as an OS), and the like. For example, when a metal oxide is used in an active layer of a transistor, the metal oxide is called an oxide semiconductor in some cases. In other words, when an OS FET is stated, it can be replaced with a transistor including an oxide or an oxide semiconductor.

Embodiment 1

(97) <Structure Example 1 of Semiconductor Device>

(98) An example of a semiconductor device including a transistor **200** of one embodiment of the present invention will be described below.

(99) Note that in this embodiment, an example in which a capacitor **100** is provided in the same layer as the transistor **200** is described. In addition, an example of using part of a structure of the transistor **200** as part of a structure of the capacitor **100** is described.

(100) In this case, part or the whole of the capacitor **100** can overlap with the transistor **200**, so that the total area of the projected area of the transistor **200** and the projected area of the capacitor **100** can be reduced, which is preferable.

(101) However, this embodiment is not limited thereto. The capacitor **100** and the transistor **200** may be provided in different layers, and for example, the capacitor **100** may be provided over an insulator (interlayer film) provided to cover the transistor **200**. Furthermore, the capacitor **100** is not necessarily provided when the semiconductor device operation or the circuit structure does not require a capacitor.

(102) FIG. **1(A)**, FIG. **1(B)**, FIG. **1(C)**, and FIG. **1(D)** are a top view and cross-sectional views of the transistor **200** of one embodiment of the present invention, the capacitor **100**, and the periphery of the transistor **200**. Note that in this specification, a semiconductor device including one capacitor and at least one transistor is referred to as a cell.

(103) FIG. **1(A)** is a top view of a cell **600** including the transistor **200** and the capacitor **100**. FIG. **1(B)**, FIG. **1(C)**, and FIG. **1(D)** are cross-sectional views of the cell **600**. Here, FIG. **1(B)** is a cross-sectional view of a portion denoted by dashed-dotted line A-B in FIG. **1(A)**, and is also a cross-sectional view of the transistor **200** in the channel length direction. FIG. **1(C)** is a cross-sectional view of a portion denoted by dashed-dotted line C-D in FIG. **1(A)**, and is also a cross-sectional view of the transistor **200** in the channel width direction. FIG. **1(D)** is a cross-sectional view of a portion denoted by dashed-dotted line E-F in FIG. **1(A)**, and is also a cross-sectional view of a connection portion between an oxide **230** and a conductor **203**, the capacitor **100**, and the like. For simplification of the drawing, some components are omitted in the top view in FIG. **1(A)**.

(104) [Cell **600**]

(105) The semiconductor device of one embodiment of the present invention includes the transistor **200**, the capacitor **100**, and an insulator **280** functioning as an interlayer film.

(106) Furthermore, a conductor **252** (a conductor **252a**, a conductor **252b**, a conductor **252c**, and a conductor **252d**) functions as a plug that is electrically connected to the transistor **200** is included.

(107) The conductor **252** is formed in contact with an inner wall of an opening in the insulator **280**. Here, a top surface of the conductor **252** can be substantially level with a top surface of the insulator **280**. Note that although the conductor **252** in the transistor **200** has a two-layer structure, the present invention is not limited thereto. For example, the conductor **252** may be a single layer or have a stacked-layer structure of three or more layers.

(108) [Transistor **200**]

(109) As illustrated in FIG. **1**, the transistor **200** includes an insulator **208** placed over a substrate (not illustrated); an insulator **210**; a conductor **203** (a conductor **203a** and a conductor **203b**) and a conductor **205** (a conductor **205a** and a conductor **205b**) that are placed over the insulator **210**; an insulator **216** provided between the conductor **203** and the conductor **205** and around the conductors; an insulator **220** placed over the insulator **216**, the conductor **203**, and the conductor **205**; an insulator **222** placed over the insulator **220**; an insulator **224** placed over the insulator **222**; an oxide **230** (an oxide **230a**, an oxide **230b**, and an oxide **230c**) placed over the insulator **224**; an insulator **250** placed over the oxide **230**; a conductor **260** (a conductor **260a** and a conductor **260b**) placed over the insulator **250**; an insulator **270** and an insulator **271** that are placed over the conductor **260**; an insulator **272** placed in contact with at least side surfaces of the insulator **250** and the conductor **260**; and an insulator **274** placed in contact with the oxide **230** and the insulator

272.

(110) Note that the insulator **216** can be formed by polishing an insulating film placed to cover the conductor **203** and the conductor **205** by a CMP method or the like to expose the conductor **203** and the conductor **205**. Thus, surfaces of the insulator **216**, the conductor **203**, and the conductor **205** have high planarity.

(111) The insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a** have an opening. The oxide **230b** is electrically connected to the conductor **203** through the opening. When the oxide **230b** is connected to the conductor **203** without through the oxide **230a**, the series resistance and the contact resistance can be reduced. With such a structure, a semiconductor device with favorable electrical characteristics can be obtained. More specifically, a transistor with an increased on-state current and a semiconductor device including the transistor can be obtained.

(112) Moreover, the conductor **203** and the conductor **205** preferably have a stacked-layer structure. Furthermore, a material that is less likely to be oxidized, that is, has a higher oxidation resistance, than a material for the conductor **203a** and the conductor **205a** is preferably used for the conductor **203b** and the conductor **205b**. When a material that is less likely to be oxidized is used for the conductor **203b** and the conductor **205b**, oxidation of the conductor **203** and the conductor **205** can be inhibited at the formation of an insulating film to be the insulator **216**, at the formation of the insulator **220**, at the formation of the opening provided in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**, and at the formation of an oxide to be the oxide **230b**. Thus, an increase in the electrical resistance due to oxidation of the conductor **203** and the conductor **205** can be inhibited. In particular, since oxidation of a top surface of the conductor **203** is inhibited, the contact between the conductor **203** and the oxide **230b** becomes favorable.

(113) For the conductor **203a** and the conductor **205a**, a material having a lower resistance than the conductor **203b** and the conductor **205b** is preferably used. The conductor **203b** and the conductor **205b** which are formed of a material with a high oxidation resistance are provided over the conductor **203a** and the conductor **205a**, respectively. Therefore, an increase in the electrical resistance due to oxidation of the conductor **203a** and the conductor **205a** or the like can be inhibited in the manufacturing process of the transistor **200** or the like.

(114) Note that although the transistor **200** has, as illustrated in FIG. 1, a structure in which the oxide **230a**, the oxide **230b**, and the oxide **230c** are stacked, the present invention is not limited thereto. For example, a two-layer structure of the oxide **230a** and the oxide **230b** or a stacked-layer structure of four or more layers may be employed. Alternatively, a single layer of only the oxide **230b** or only the oxide **230b** and the oxide **230c** may be provided. Although the transistor **200** has a structure in which the conductor **260a** and the conductor **260b** are stacked, the present invention is not limited thereto. For example, a single layer or a stacked-layer structure of three or more layers may be employed.

(115) Here, an enlarged view of a region **239** in the vicinity of a channel, which is surrounded by a dashed-dotted line in FIG. 1(B), is illustrated in FIG. 2.

(116) As illustrated in FIG. 1(B) and FIG. 2, the oxide **230** includes a region **232** (a region **232a** and a region **232b**) between a region **234** functioning as a channel formation region of the transistor **200** and a region **231** (a region **231a** and a region **231b**) functioning as a source region or a drain region. The region **231** functioning as the source region or the drain region is a region having a high carrier density and reduced resistance. In addition, the region **234** functioning as the channel formation region is a region having a lower carrier density than the region **231** functioning as the source region or the drain region. Moreover, the region **232** is a region having a lower carrier density than the region **231** functioning as the source region or the drain region and having a higher carrier density than the region **234** functioning as the channel formation region. That is, the region **232** functions as a junction region between the channel formation region and the source region or the drain region.

(117) When the junction region is provided, a high-resistance region is not formed between the region **231** functioning as the source region or the drain region and the region **234** functioning as the channel formation region, thereby increasing on-state current of the transistor.

(118) The region **232** includes a region overlapping with the conductor **260** functioning as a gate electrode. In particular, the region overlapping with the conductor **260** functioning as the gate electrode in the region **232** sometimes functions as a so-called overlap region (also referred to as an Lov region).

(119) The region **231** is preferably in contact with the insulator **274**. Furthermore, the concentration of at least one of a metal element such as indium and an impurity element such as hydrogen or nitrogen in the region **231** is preferably higher than that in each of the region **232** and the region **234**.

(120) The region **232** includes a region overlapping with the insulator **272**. The concentration of at least one of a metal element such as indium and an impurity element such as hydrogen or nitrogen in the region **232** is preferably higher than that in the region **234**. On the other hand, the concentration of at least one of a metal element such as indium and an impurity element such as hydrogen or nitrogen is preferably lower than that in the region **231**.

(121) The region **234** overlaps with the conductor **260**. The region **234** is placed between the region **232a** and the region **232b**, and the concentration of at least one of a metal element such as indium and an impurity element such as hydrogen or nitrogen in the region **234** is preferably lower than that in each of the region **231** and the region **232**.

(122) In addition, in the oxide **230**, boundaries between the region **231**, the region **232**, and the region **234** cannot be observed clearly in some cases. The concentration of a metal element such as indium and an impurity element such as hydrogen or nitrogen, which is detected in each region, may be gradually changed (such a change is also referred to as gradation) not only between the regions but also in each region. That is, the region closer to the region **234**, from the region **231** to the region **232**, preferably has a lower concentration of a metal element such as indium and an impurity element such as hydrogen or nitrogen.

(123) Furthermore, in FIG. **1(B)** and FIG. **2**, the region **234**, the region **231**, and the region **232** are formed in the oxide **230b**; however, the present invention is not limited thereto, and these regions may be formed in the oxide **230a** or the oxide **230c**, for example. Although the boundaries between the regions are indicated substantially perpendicularly to a top surface of the oxide **230** in the drawings, this embodiment is not limited thereto. For example, the region **232** may project to the conductor **260** side in the vicinity of the surface of the oxide **230b**, and recede to the conductor **252a** side or the conductor **252b** side in the vicinity of a bottom surface of the oxide **230b**.

(124) Note that in the transistor **200**, a metal oxide functioning as an oxide semiconductor (hereinafter, also referred to as an oxide semiconductor) is preferably used for the oxide **230**. A transistor including an oxide semiconductor has an extremely low leakage current (off-state current) in a non-conduction state; thus, a semiconductor device with low power consumption can be provided. Moreover, an oxide semiconductor can be deposited by a sputtering method or the like and thus can be used for a transistor included in a highly integrated semiconductor device.

(125) Meanwhile, the transistor including an oxide semiconductor is likely to have its electrical characteristics changed by impurities and oxygen vacancies in the oxide semiconductor; as a result, the reliability is reduced, in some cases. Hydrogen in an oxide semiconductor reacts with oxygen bonded to a metal atom to be water, and thus causes an oxygen vacancy, in some cases. Entry of hydrogen into the oxygen vacancy generates an electron serving as a carrier in some cases.

Accordingly, a transistor including an oxide semiconductor containing oxygen vacancies in a channel formation region is likely to have normally-on characteristics. Thus, it is preferable that oxygen vacancies in the channel formation region be reduced as much as possible.

(126) In particular, when oxygen vacancies exist at an interface between the region **234** of the oxide **230** where a channel is formed and the insulator **250** functioning as a gate insulating film, a

variation in the electrical characteristics is likely to occur and the reliability is reduced in some cases.

(127) In view of the above, the insulator **250** overlapping with the region **234** of the oxide **230** preferably contains oxygen at a higher proportion than oxygen in the stoichiometric composition (also referred to as excess oxygen). That is, excess oxygen in the insulator **250** is diffused into the region **234**, whereby oxygen vacancies in the region **234** can be reduced.

(128) The insulator **272** is preferably provided in contact with the insulator **250**. For example, the insulator **272** preferably has a function of inhibiting diffusion of oxygen (for example, at least one of oxygen atoms and oxygen molecules), that is, the above oxygen is preferably less likely to pass through the insulator **272**. When the insulator **272** has a function of inhibiting diffusion of oxygen, oxygen in an excess-oxygen region is not diffused to the insulator **274** side and is supplied to the region **234** efficiently. Thus, the formation of oxygen vacancies at the interface between the oxide **230** and the insulator **250** is inhibited, leading to an improvement in the reliability of the transistor **200**.

(129) Furthermore, the transistor **200** is preferably covered with the insulator which has a barrier property and prevents entry of impurities such as water and hydrogen. The insulator having a barrier property is an insulator containing an insulating material having a function of inhibiting diffusion of impurities such as a hydrogen atom, a hydrogen molecule, a water molecule, a nitrogen atom, a nitrogen molecule, a nitrogen oxide molecule (N.sub.2O, NO, NO.sub.2, and the like), and a copper atom (an insulating material through which the above impurities are less likely to pass). Moreover, it is preferable to use an insulating material having a function of inhibiting diffusion of oxygen (for example, at least one of oxygen atoms and oxygen molecules), that is, an insulating material through which the above oxygen is less likely to pass.

(130) The structure of a semiconductor device including the transistor **200** of one embodiment of the present invention will be described in detail below.

(131) In the transistor **200**, the conductor **260** functions as a first gate electrode in some cases. Furthermore, the conductor **205** functions as a second gate electrode in some cases. In that case, by changing a potential applied to the conductor **205** not in synchronization with but independently of a potential applied to the conductor **260**, the threshold voltage of the transistor **200** can be controlled. In particular, by applying a negative potential to the conductor **205**, the threshold voltage of the transistor **200** can be higher than 0 V, and the off-state current can be reduced. Accordingly, a drain current when a voltage applied to the conductor **260** is 0 V can be reduced.

(132) The conductor **205** functioning as the second gate electrode is placed to overlap with the oxide **230** and the conductor **260**.

(133) Here, the conductor **205** is preferably provided to be long so that the length in the channel width direction is greater than that of the region **234** of the oxide **230**. It is particularly preferable that the conductor **205** extend beyond an end portion of the region **234** of the oxide **230** that intersects with the channel width direction. That is, the conductor **205** and the conductor **260** preferably overlap with each other with the insulator therebetween on a side surface of the oxide **230** in the channel width direction.

(134) The conductor **203** can be formed in the same step as the conductor **205**. The conductor **203** functions as an electrode or a wiring that is electrically connected to the region **231** of the oxide **230**.

(135) The insulator **216** is formed between the conductor **203** and the conductor **205** and around these conductors. Here, the top surfaces of the conductor **203** and the conductor **205** can be substantially level with a top surface of the insulator **216**.

(136) Here, a conductive material that is less likely to be oxidized, that is, has a higher oxidation resistance, than a material for the conductor **203a** and the conductor **205a** is preferably used for the conductor **203b** and the conductor **205b**. As such a conductive material, a metal nitride such as tantalum nitride or titanium nitride can be used.

(137) By using a material with a high oxidation resistance for the conductor **203b** and the conductor **205b**, the conductivity of the conductor **203** and the conductor **205** can be prevented from being reduced because of oxidation. Furthermore, oxidation of the top surface of the conductor **203** is inhibited, so that the contact between the oxide **230b** and the conductor **203** becomes favorable.

(138) In addition, a conductive material containing tungsten, copper, or aluminum as its main component is preferably used for the conductor **203a** and the conductor **205a**. In this embodiment, tungsten is used for the conductor **203a** and the conductor **205a**.

(139) As illustrated in FIG. 3, a conductor **209** electrically connected to the conductor **205** may be provided. An insulator **212** is provided over the insulator **210**, and the conductor **209** can be formed to be embedded in an opening provided in the insulator **212**. In that case, the conductor **209** may have a stacked-layer structure of a first conductor provided in contact with a side surface and a bottom surface of the opening provided in the insulator **212** and a second conductor provided over the first conductor. In this case, the first conductor is preferably a conductive barrier. Alternatively, the conductor **209** may have a single-layer structure or a stacked-layer structure of three or more layers. In the case where the conductor **209** has a stacked-layer structure of three or more layers, two or more conductive barriers may be provided. As the conductive barrier, one or more barrier films selected from a barrier film inhibiting passage of impurities such as hydrogen, water, and nitrogen, a barrier film inhibiting passage of oxygen, and a barrier film inhibiting passage of a metal component can be provided.

(140) Alternatively, the conductor **209** may be formed by a lithography method or an etching method after a conductive film that is formed of a single layer or two or more layers is provided over the insulator **210**. Furthermore, an insulating film may be formed over the insulator **210** to cover the conductor **209** and the insulating film is processed by a CMP method or an etching method, so that the insulator **212** is formed.

(141) The conductor **209** can function as an electrode or a wiring. When the conductor **205** is used as the second gate electrode of the transistor **200**, part of the conductor **209** can function as a gate wiring. In that case, the conductor **205** and the conductor **252d** may be electrically connected to each other through a conductor **207** including a conductor **207a** and a conductor **207b** formed over the conductor **207a**, and the conductor **209**. The conductor **207** can be formed in the same step as the conductor **203** and the conductor **205**.

(142) The conductor **209** is electrically connected to the oxide **230b** through the conductor **203**, and can function as a source wiring or a drain wiring of the transistor **200**. The conductor **209** may be used as an electrode for electrical connection with an element or a wiring positioned below the insulator **210**.

(143) The insulator **210** preferably functions as an insulating barrier film for preventing impurities such as water and hydrogen from entering the transistor from the substrate side. Accordingly, an insulating material having a function of inhibiting diffusion of impurities such as a hydrogen atom, a hydrogen molecule, a water molecule, a nitrogen atom, a nitrogen molecule, a nitrogen oxide molecule (N.sub.2O, NO, NO.sub.2, and the like), and a copper atom (an insulating material through which the above impurities are less likely to pass) is preferably used for the insulator **210**. Moreover, it is preferable to use an insulating material having a function of inhibiting diffusion of oxygen (for example, at least one of oxygen atoms and oxygen molecules), that is, an insulating material through which the above oxygen is less likely to pass.

(144) For example, aluminum oxide or silicon nitride is preferably used for the insulator **210**. Thus, impurities such as hydrogen and water can be inhibited from being diffused to the transistor side from the insulator **210**. In addition, oxygen in the insulator **224** and the like can be inhibited from being diffused to the substrate side from the insulator **210**.

(145) Moreover, the insulator **208**, the insulator **216**, and the insulator **280** functioning as interlayer films preferably have a lower permittivity than the insulator **210**. In the case where a material with

a low permittivity is used for an interlayer film, the parasitic capacitance generated between wirings can be reduced.

(146) For example, for the insulator **208**, the insulator **216**, and the insulator **280** functioning as interlayer films, a single layer or stacked layers of any of insulators such as silicon oxide, silicon oxynitride, silicon nitride oxide, aluminum oxide, hafnium oxide, tantalum oxide, zirconium oxide, lead zirconate titanate (PZT), strontium titanate (SrTiO_3), and $(\text{Ba,Sr})\text{TiO}_3$ (BST) can be used.

(147) Alternatively, aluminum oxide, bismuth oxide, germanium oxide, niobium oxide, silicon oxide, titanium oxide, tungsten oxide, yttrium oxide, or zirconium oxide may be added to the insulator, for example. Alternatively, the insulator may be subjected to nitriding treatment. Silicon oxide, silicon oxynitride, or silicon nitride may be stacked over the insulator.

(148) The insulator **220**, the insulator **222**, and the insulator **224** each function as a gate insulator.

(149) Here, as the insulator **224** in contact with the oxide **230**, an oxide insulator that contains more oxygen than that in the stoichiometric composition is preferably used. That is, an excess-oxygen region is preferably formed in the insulator **224**. When such an insulator containing excess oxygen is provided in contact with the oxide **230**, oxygen vacancies in the oxide **230** can be reduced, leading to an improvement in reliability.

(150) As the insulator including the excess-oxygen region, specifically, an oxide material that releases part of oxygen by heating is preferably used. An oxide that releases part of oxygen by heating is an oxide film of which the amount of released oxygen converted into oxygen atoms is greater than or equal to 1.0×10^{18} atoms/cm³, preferably greater than or equal to 3.0×10^{20} atoms/cm³ in TDS (Thermal Desorption Spectroscopy) analysis. Note that the temperature of the film surface in the TDS analysis is preferably in a range higher than or equal to 100° C. and lower than or equal to 700° C., or higher than or equal to 100° C. and lower than or equal to 400° C.

(151) Furthermore, in the case where the insulator **224** includes an excess-oxygen region, the insulator **222** preferably has a function of inhibiting diffusion of oxygen (for example, at least one of oxygen atoms and oxygen molecules), that is, the above oxygen is preferably less likely to pass through the insulator **222**.

(152) When the insulator **222** has a function of inhibiting diffusion of oxygen, oxygen in the excess-oxygen region is not diffused to the insulator **220** side and can be supplied to the oxide **230** efficiently. The conductor **205** can be inhibited from reacting with oxygen in the excess-oxygen region of the insulator **224**.

(153) For the insulator **222**, a single layer or stacked layers of an insulator containing what is called a high-k material such as aluminum oxide, hafnium oxide, hafnium aluminate, tantalum oxide, zirconium oxide, lead zirconate titanate (PZT), strontium titanate (SrTiO_3), or $(\text{Ba,Sr})\text{TiO}_3$ (BST) are preferably used, for example. When a high-k material is used for the insulator functioning as a gate insulator, miniaturization and high integration of the transistor become possible. It is particularly preferable to use an insulating material having a function of inhibiting diffusion of impurities such as aluminum oxide and hafnium oxide, and hafnium aluminate, oxygen, and the like (an insulating material through which the above oxygen is less likely to pass). The insulator **222** formed using such a material functions as a layer that prevents release of oxygen from the oxide **230** and entry of impurities such as hydrogen from the periphery of the transistor **200**.

(154) Alternatively, aluminum oxide, bismuth oxide, germanium oxide, niobium oxide, silicon oxide, titanium oxide, tungsten oxide, yttrium oxide, or zirconium oxide may be added to the insulator, for example. Alternatively, the insulator may be subjected to nitriding treatment. Silicon oxide, silicon oxynitride, or silicon nitride may be stacked over the insulator.

(155) It is preferable that the insulator **220** be thermally stable. Because silicon oxide and silicon oxynitride are thermally stable, combination of silicon oxide or silicon oxynitride with an insulator

which is a high-k material allows the stacked-layer structure to be thermally stable and have a high relative permittivity, for example.

(156) Note that the insulator **220**, the insulator **222**, and the insulator **224** may each have a stacked-layer structure of two or more layers. In this case, the stacked-layer structure is not limited to a stacked-layer structure including the same material but may be a stacked-layer structure including different materials. The insulator **220**, the insulator **222**, and the insulator **224** functioning as gate insulators in the transistor **200** are described; however, this embodiment is not limited thereto. For example, two layers or one layer of any of the insulator **220**, the insulator **222**, and the insulator **224** may be provided as a gate insulator.

(157) The oxide **230** includes the oxide **230a**, the oxide **230b** over the oxide **230a**, and the oxide **230c** over the oxide **230b**. The oxide **230** also includes the region **231**, the region **232**, and the region **234**. Note that at least part of the region **231** is preferably in contact with the insulator **274**. Moreover, it is preferable that the concentration of at least one of hydrogen, nitrogen, and a metal element such as indium in at least part of the region **231** be higher than that in the region **234**.

(158) When the transistor **200** is turned on, the region **231a** or the region **231b** functions as the source region or the drain region. In addition, at least part of the region **234** functions as a region where a channel is formed.

(159) The insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a** have an opening, and the region **231** of the oxide **230b** is electrically connected to the conductor **203**. That is, one of a source and a drain of the transistor **200** is electrically connected to the conductor **203** through the opening provided in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**, and the conductor **203** can function as one of a source electrode and a drain electrode, or one of a source wiring and a drain wiring.

(160) As illustrated in FIG. 1(A) and FIG. 1(D), in order to cover the opening formed in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**, the oxide **230a** and the oxide **230b** are each preferably formed to have a wider width in the E-F direction than the opening in the region overlapping with the opening. Therefore, the widths of the oxide **230a** and the oxide **230b** in the E-F direction in that region may be wider than the widths of the oxide **230a** and the oxide **230b** in the C-D direction in a region where a channel is formed or a region on the A side. With such a structure, contact between the oxide **230b** and the conductor **203** can be assured. Furthermore, the area of the capacitor **100** can be increased, and an increase in the capacity of the capacitor **100** can be expected.

(161) Here, as illustrated in FIG. 2, the oxide **230** preferably includes the region **232**. With this structure, the transistor **200** can have a high on-state current and a low leakage current (off-state current) in a non-conduction state.

(162) When the oxide **230b** is provided over the oxide **230a**, impurities can be inhibited from being diffused into the oxide **230b** from the components formed below the oxide **230a**. Moreover, when the oxide **230b** is below the oxide **230c**, impurities can be inhibited from being diffused into the oxide **230b** from the components formed above the oxide **230c**.

(163) The oxide **230** has a curved surface between the side surface and the top surface. That is, an end portion of the side surface and an end portion of the top surface are preferably curved (hereinafter also referred to as a round shape). The radius of curvature of the curved surface at an end portion of the oxide **230b** is greater than or equal to 3 nm and less than or equal to 10 nm, preferably greater than or equal to 5 nm and less than or equal to 6 nm, for example.

(164) As the oxide **230**, a metal oxide functioning as an oxide semiconductor (hereinafter, also referred to as an oxide semiconductor) is preferably used. For example, a metal oxide having an energy gap of 2 eV or more, preferably 2.5 eV or more is preferably used for the metal oxide to be the region **234**. With the use of a metal oxide having such a wide energy gap, the off-state current of the transistor can be reduced.

(165) Note that in this specification and the like, a metal oxide containing nitrogen is also called a

metal oxide in some cases. Alternatively, a metal oxide containing nitrogen may be called a metal oxynitride.

(166) A transistor including an oxide semiconductor has an extremely low leakage current in a non-conduction state; thus, a semiconductor device with low power consumption can be provided. Moreover, an oxide semiconductor can be deposited by a sputtering method or the like and thus can be used for a transistor included in a highly integrated semiconductor device.

(167) For example, as the oxide **230**, a metal oxide such as an In-M-Zn oxide (the element M is one or more kinds selected from aluminum, gallium, yttrium, copper, vanadium, beryllium, boron, silicon, titanium, iron, nickel, germanium, zirconium, molybdenum, lanthanum, cerium, neodymium, hafnium, tantalum, tungsten, magnesium, and the like) is used. An In—Ga oxide or an In—Zn oxide may be used as the oxide **230**.

(168) Here, the region **234** of the oxide **230** will be described.

(169) The region **234** preferably has a stacked-layer structure of oxides which differ in the atomic ratio of metal elements. Specifically, in the case of the stacked-layer structure of the oxide **230a** and the oxide **230b**, the atomic ratio of the element M to constituent elements in the metal oxide used as the oxide **230a** is preferably greater than the atomic ratio of the element M to constituent elements in the metal oxide used as the oxide **230b**. Moreover, the atomic ratio of the element M to In in the metal oxide used as the oxide **230a** is preferably greater than the atomic ratio of the element M to In in the metal oxide used as the oxide **230b**. Moreover, the atomic ratio of In to the element M in the metal oxide used as the oxide **230b** is preferably greater than the atomic ratio of In to the element M in the metal oxide used as the oxide **230a**. As the oxide **230c**, a metal oxide which can be used as the oxide **230a** or the oxide **230b** can be used.

(170) As the oxide **230a**, for example, a metal oxide having a composition of In:Ga:Zn=1:3:4, In:Ga:Zn=1:3:2, or In:Ga:Zn=1:1:1 can be used. As the oxide **230b**, for example, a metal oxide having a composition of In:Ga:Zn=4:2:3, In:Ga:Zn=1:1:1, or In:Ga:Zn=5:1:6 can be used. As the oxide **230c**, for example, a metal oxide having a composition of In:Ga:Zn=1:3:4, In:Ga:Zn=1:3:2, In:Ga:Zn=4:2:3, or In:Ga:Zn=1:1:1 can be used. Note that the above composition represents the atomic ratio of an oxide formed over a substrate or the atomic ratio of a sputtering target.

(171) A combination of a metal oxide having a composition of In:Ga:Zn=1:3:4 as the oxide **230a**, a metal oxide having a composition of In:Ga:Zn=4:2:3 as the oxide **230b**, and a metal oxide having a composition of In:Ga:Zn=1:3:4 as the oxide **230c**, or a combination of a metal oxide having a composition of In:Ga:Zn=1:3:4 as the oxide **230a**, a metal oxide having a composition of In:Ga:Zn=4:2:3 as the oxide **230b**, and a metal oxide having a composition of In:Ga:Zn=1:1:1 as the oxide **230c** is particularly preferable because the oxide **230b** can be interposed between the oxide **230a** and the oxide **230c** each having a wider energy gap. Here, each of the oxide **230a** and the oxide **230c** having a wide energy gap is referred to as a wide gap, and the oxide **230b** having a relatively narrow energy gap is referred to as a narrow gap in some cases. The wide gap and the narrow gap are described in [Composition of metal oxide].

(172) Next, the region **231** and the region **232** which are included in the oxide **230** will be described.

(173) The region **231** and the region **232** are regions whose resistance is reduced by addition of a metal atom such as indium or impurities to a metal oxide provided as the oxide **230**. Note that each of the regions has higher conductivity than at least the oxide **230b** in the region **234**. Note that for addition of impurities to the region **231** and the region **232**, for example, a dopant which is at least one of a metal element such as indium and impurities is added by plasma treatment, an ion implantation method by which an ionized source gas is subjected to mass separation and then added, an ion doping method by which an ionized source gas is added without mass separation, a plasma immersion ion implantation method, or the like.

(174) That is, when the content of a metal atom such as indium in the region **231** and the region **232** of the oxide **230** is increased, the electron mobility can be increased and the resistance can be

reduced.

(175) Furthermore, when the insulator **274** containing impurity elements is deposited in contact with the oxide **230**, impurities can be added to the region **231** and the region **232**.

(176) That is, the resistance of the region **231** and the region **232** to which an element that forms an oxygen vacancy or an element trapped by an oxygen vacancy is added is reduced. Typical examples of the element are hydrogen, boron, carbon, nitrogen, fluorine, phosphorus, sulfur, chlorine, titanium, and a rare gas. Typical examples of the rare gas element are helium, neon, argon, krypton, and xenon. Accordingly, the region **231** and the region **232** are made to contain one or more of the above elements.

(177) Alternatively, as the insulator **274**, a film which extracts and absorbs oxygen in the region **231** and the region **232** may be used. When oxygen is extracted, oxygen vacancies are generated in the region **231** and the region **232**. Hydrogen, boron, carbon, nitrogen, fluorine, phosphorus, sulfur, chlorine, titanium, a rare gas, or the like is trapped by oxygen vacancies, whereby the resistance of the region **231** and the region **232** is reduced.

(178) The insulator **274** may be formed of a single layer or may have a stacked-layer structure of two or more layers. The insulator **274** can be formed by a CVD method, an ALD method, a sputtering method, or the like. An ALD method is favorable for deposition on a step portion formed by the oxide **230** or the conductor **260** because of its excellent step coverage, excellent thickness uniformity, and excellent thickness controllability. An insulator with a thickness of greater than or equal to 0.5 nm and less than or equal to 5.0 nm may be formed by an ALD method, and then an insulator with a thickness of greater than or equal to 1.0 nm and less than or equal to 10.0 nm may be stacked thereover by a plasma CVD method, so that the insulator **274** may be formed. For example, over aluminum oxide, hafnium oxide, or an oxide containing aluminum and hafnium (hafnium aluminate) formed by an ALD method, silicon nitride, silicon nitride oxide, silicon oxynitride, or silicon oxide formed by a plasma CVD method is stacked, so that the insulator **274** may be formed. Alternatively, an insulator with a thickness of greater than or equal to 1.0 nm and less than or equal to 10.0 nm may be formed to be a single-layer insulator **274** by a plasma CVD method. For example, silicon nitride, silicon nitride oxide, silicon oxynitride, or silicon oxide formed by a plasma CVD method may be the insulator **274**.

(179) When the region **232** is provided in the transistor **200**, a high-resistance region is not formed between the region **231** functioning as the source region or the drain region and the region **234** where a channel is formed, so that the on-state current and the mobility of the transistor can be increased. Since the gate does not overlap with the source region and the drain region in the channel length direction owing to the region **232**, formation of unnecessary capacitance can be inhibited. Furthermore, leakage current in a non-conduction state can be reduced by including the region **232**.

(180) Thus, by appropriately selecting the area of the region **232**, a transistor having electrical characteristics necessary for the circuit design can be easily provided.

(181) The insulator **250** functions as a gate insulating film. The insulator **250** is preferably placed in contact with a top surface of the oxide **230c**. The insulator **250** is preferably formed using an insulator from which oxygen is released by heating. The insulator **250** is an oxide film of which the amount of released oxygen converted into oxygen atoms is greater than or equal to 1.0×10^{18} atoms/cm³, preferably greater than or equal to 3.0×10^{20} atoms/cm³ in thermal desorption spectroscopy analysis (TDS analysis), for example. Note that the temperature of the film surface in the TDS analysis is preferably in a range higher than or equal to 100° C. and lower than or equal to 700° C., or higher than or equal to 100° C. and lower than or equal to 500° C.

(182) When an insulator from which oxygen is released by heating is provided as the insulator **250** in contact with the top surface of the oxide **230c**, oxygen can be effectively supplied to the region **234** of the oxide **230b**. Furthermore, as in the insulator **224**, the concentration of impurities such as water and hydrogen in the insulator **250** is preferably reduced. The thickness of the insulator **250** is

preferably greater than or equal to 1 nm and less than or equal to 20 nm.

(183) The conductor **260** functioning as the first gate electrode includes the conductor **260a** and the conductor **260b** over the conductor **260a**.

(184) Titanium nitride or the like is preferably used for the conductor **260a**. Moreover, a metal with high conductivity such as tungsten can be used for the conductor **260b**, for example.

(185) Alternatively, a conductor formed of a conductive oxide may be provided between the insulator **250** and the conductor **260a**. For example, the metal oxide that can be used as the oxide **230a** or the oxide **230b** can be used. In particular, an In—Ga—Zn-based oxide with a metal atomic ratio of [In]:[Ga]:[Zn]=4:2:3 to 4.1 or in the neighborhood thereof, which has high conductivity, is preferably used. When such a conductor is provided over the insulator **250**, oxygen can be inhibited from entering the conductor **260a**, and an increase in electric resistance value of the conductor **260a** due to oxidation can be prevented.

(186) When the above conductive oxide is deposited by a sputtering method, oxygen can be added to the insulator **250**, so that oxygen can be supplied to the oxide **230b**. Thus, oxygen vacancies in the region **234** of the oxide **230** can be reduced.

(187) Alternatively, the insulator **270** functioning as a barrier film may be placed over the conductor **260c**. For the insulator **270**, an insulating material that has a function of inhibiting passage of oxygen and impurities such as water and hydrogen is preferably used. For example, an insulator containing oxides of one or both of aluminum and hafnium can be used. Aluminum oxide, hafnium oxide, an oxide containing aluminum and hafnium (hafnium aluminate), or the like is preferably used for the insulator containing oxides of one or both of aluminum and hafnium. Thus, oxidation of the conductor **260** can be prevented. This can also prevent entry of impurities such as water and hydrogen into the oxide **230** through the conductor **260** and the insulator **250**.

(188) Furthermore, the insulator **271** functioning as a hard mask is preferably placed over the insulator **270**. By provision of the insulator **270**, in processing the conductor **260**, the side surface of the conductor **260** can be substantially perpendicular, specifically, an angle formed by the side surface of the conductor **260** and a surface of the substrate can be greater than or equal to 75° and less than or equal to 100°, preferably greater than or equal to 80° and less than or equal to 95°. When the conductor is processed into such a shape, the insulator **272** that is subsequently formed can be formed into a desired shape.

(189) The insulator **272** functioning as a barrier film is provided in contact with the side surfaces of the insulator **250**, the conductor **260**, and the insulator **270**.

(190) Here, for the insulator **272**, an insulating material that has a function of inhibiting passage of oxygen and impurities such as water and hydrogen is preferably used. For example, an insulator containing oxides of one or both of aluminum and hafnium can be used. Aluminum oxide, hafnium oxide, an oxide containing aluminum and hafnium (hafnium aluminate), or the like is preferably used for the insulator containing oxides of one or both of aluminum and hafnium. In this manner, oxygen in the insulator **250** can be prevented from being diffused to the outside. In addition, impurities such as hydrogen and water can be inhibited from entering the oxide **230** from the end portion of the insulator **250** or the like.

(191) By provision of the insulator **272**, a top surface and the side surface of the conductor **260** and the side surface of the insulator **250** can be covered with the insulator having a function of inhibiting passage of oxygen and impurities such as water and hydrogen. This can prevent entry of impurities such as water and hydrogen into the oxide **230** through the conductor **260** and the insulator **250**. Thus, the insulator **272** functions as a side barrier for protecting the side surfaces of the gate electrode and the gate insulating film.

(192) In the case where the transistor is miniaturized and formed so that a channel length is approximately greater than or equal to 10 nm and less than or equal to 30 nm, impurity elements in the structure bodies provided in the vicinity of the transistor **200** might be diffused, and the region **231a** and the region **231b**, or the region **232a** and the region **232b** might be electrically connected

to each other.

(193) In view of the above, the insulator **272** is formed as described in this embodiment so that impurities such as hydrogen and water can be inhibited from entering the insulator **250** and the conductor **260**, and oxygen in the insulator **250** can be prevented from being diffused to the outside. Accordingly, when a first gate voltage is 0 V, the source region and the drain region can be prevented from being electrically connected to each other directly or through the region **232** or the like.

(194) The insulator **274** is provided to cover the insulator **271**, the insulator **272**, the oxide **230**, the insulator **224**, and the like.

(195) Moreover, for the insulator **274**, an insulating material having a function of inhibiting passage of oxygen and impurities such as water and hydrogen is preferably used. For example, for the insulator **274**, silicon nitride, silicon nitride oxide, silicon oxynitride, aluminum nitride, or aluminum nitride oxide is preferably used. Alternatively, the insulating material may be stacked over aluminum oxide, hafnium oxide, or an oxide containing aluminum and hafnium (hafnium aluminate), so that the insulator **274** may be formed. When such an insulator **274** is formed, entry of oxygen through the insulator **274** and supply of oxygen to oxygen vacancies in the region **231a** and the region **231b**, which decrease the carrier density, can be prevented. Furthermore, it is possible to prevent impurities such as water and hydrogen from passing through the insulator **274** and the region **231a** and the region **231b** from excessively enlarging to the region **234** side.

(196) Note that when the region **231** and the region **232** are formed by deposition of the insulator **274**, the insulator **274** preferably contains an element that forms an oxygen vacancy in the oxide **230** or an element trapped by the oxygen vacancy in the oxide **230**. Typical examples of the element are hydrogen, boron, carbon, nitrogen, fluorine, phosphorus, sulfur, chlorine, titanium, and a rare gas. Typical examples of the rare gas element are helium, neon, argon, krypton, and xenon. When an insulator containing such an element is used as the insulator **274**, the element is added to the oxide **230**, so that the region **231** and the region **232** can be formed in the oxide **230**.

(197) Alternatively, as the insulator **274**, a film which extracts and absorbs oxygen in the region **231** and the region **232** may be used. When oxygen is extracted, oxygen vacancies are generated in the region **231** and the region **232**. Hydrogen, boron, carbon, nitrogen, fluorine, phosphorus, sulfur, chlorine, titanium, a rare gas, or the like is trapped by oxygen vacancies, whereby the resistance of the region **231** and the region **232** is reduced.

(198) In the case where the capacitor **100** is provided in the same layer as the transistor **200**, a conductor **130** is provided to overlap with the region **231** of the oxide **230** that functions as one electrode of the capacitor with the insulator **274** interposed therebetween.

(199) The insulator **280** functioning as an interlayer film is preferably provided over the insulator **274**, or over the insulator **274** and the conductor **130** in the case where the conductor **130** is provided over the insulator **274**. As in the insulator **224** or the like, the concentration of impurities such as water and hydrogen in the insulator **280** is preferably reduced. Note that the insulator **280** may have a stacked-layer structure of similar insulators.

(200) Next, the conductor **252** (the conductor **252a**, the conductor **252b**, the conductor **252c**, and the conductor **252d**) electrically connected to the transistor **200** is provided. The conductor **252a** electrically connected to the oxide **230** is placed in an opening formed in the insulator **280** and the insulator **274**, the conductor **252b** electrically connected to the conductor **130** is placed in the opening formed in the insulator **280**, the conductor **252c** electrically connected to the conductor **260** functioning as the first gate is placed in the opening formed in the insulator **280**, the insulator **274**, the insulator **271**, and the insulator **270**, and the conductor **252d** electrically connected to the conductor **205** functioning as the second gate is placed in an opening formed in the insulator **280**, the insulator **274**, the insulator **224**, the insulator **222**, and the insulator **220**. Note that in the case where the conductor **130** is not provided, the conductor **252b** can be electrically connected to the oxide **230** through the opening formed in the insulator **280** and the insulator **274**. Note that top

surfaces of the conductor **252a**, the conductor **252b**, the conductor **252c**, and the conductor **252d** may be on the same plane as the top surface of the insulator **280**.

(201) The opening provided with the conductor **252b** is preferably provided to overlap with at least part of the conductor **203** and at least part of the opening provided in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**, in which case miniaturization and high integration of the semiconductor device can be achieved.

(202) Note that the conductor **252** can be formed by a damascene method.

(203) The conductor **252a** is in contact with the region **231a** functioning as one of a source region and a drain region of the transistor **200**. In addition, the conductor **203** is in contact with the region **231b** functioning as the other of the source region and the drain region of the transistor **200**. Because the resistance of the region **231a** and the region **231b** is reduced, the contact resistance between the conductor **252a** and the region **231a** and the contact resistance between the conductor **203** and the region **231b** are reduced, leading to a high on-state current of the transistor **200**.

(204) Here, the conductor **252a** is in contact with at least the top surface of the oxide **230**, preferably also in contact with the side surface of the oxide **230**. It is particularly preferable that the conductor **252a** be in contact with one or both of the side surface on the C side and the side surface on the D side, which intersect with the channel width direction of the oxide **230**. Moreover, the conductor **252a** may be in contact with the side surface on the A side, which intersects with the channel width direction of the oxide **230**. When the conductor **252a** is in contact with the side surface of the oxide **230** in addition to the top surface of the oxide **230** as described above, the contact area of the contact portion of the conductor **252a** and the oxide **230** can be increased without an increase in the area of a top surface of the contact portion, so that the contact resistance between the conductor **252a** and the oxide **230** can be reduced. Accordingly, miniaturization of the source electrode and the drain electrode of the transistor can be achieved and, in addition, the on-state current can be increased.

(205) FIG. 1(D) illustrates a cross section of a connection portion between the conductor **203** and the oxide **230**, and the capacitor **100**. The conductor **130** is preferably wider in the E-F direction than the oxide **230**. Accordingly, capacitance can be formed not only by the top surface of the oxide **230** and the conductor **130** but also by the side surface of the oxide **230** and the conductor **130**, and thus capacitance can be increased.

(206) The conductor **252** can be formed of a first conductor in contact with the inner wall of the opening and a second conductor provided on the inner side. Here, top surfaces of the first conductor and the second conductor can be substantially level with the top surface of the insulator **280**. Note that although an example in which a two-layer conductor is used as the conductor **252** is described in this embodiment, the conductor is not limited thereto. The conductor **252** may be formed using a single layer or a stacked film of three or more layers.

(207) Here, a conductive material having a function of inhibiting diffusion of impurities such as a hydrogen atom, a hydrogen molecule, a water molecule, a nitrogen atom, a nitrogen molecule, a nitrogen oxide molecule (N.sub.2O, NO, NO.sub.2, and the like), and a copper atom (a conductive material through which the above impurities are less likely to pass) is preferably used for the first conductor used for the conductor **252**. Moreover, it is preferable to use a conductive material having a function of inhibiting diffusion of oxygen (for example, at least one of oxygen atoms and oxygen molecules), that is, a conductive material through which the above oxygen is less likely to pass. Note that in this specification, a function of inhibiting diffusion of impurities or oxygen means a function of inhibiting diffusion of any one or all of the above impurities and the above oxygen. In this specification, a conductor having such a function is referred to as a conductive barrier film in some cases.

(208) When the first conductor used for the conductor **252** has a function of inhibiting diffusion of oxygen, it is possible to prevent absorption of oxygen in the insulator **280** by the second conductor used for the conductor **252** and a decrease in the conductivity due to oxidation. For the conductive

material having a function of inhibiting diffusion of oxygen, for example, titanium, titanium nitride, tantalum, tantalum nitride, ruthenium, or ruthenium oxide is preferably used. Thus, the first conductor used for the conductor **252** is a single layer or stacked layers of the above conductive materials. Furthermore, when the first conductor used for the conductor **252** has a function of preventing diffusion of impurities such as hydrogen, water, and nitrogen, entry of impurities such as hydrogen and water into the transistor **200** from above the insulator **280** through the conductor **252**. In this embodiment, titanium nitride is used as the first conductor used for the conductor **252**.

(209) Moreover, for the second conductor used for the conductor **252**, a conductive material containing tungsten, copper, or aluminum as its main component is preferably used. In this embodiment, tungsten is used for the second conductor used for the conductor **252**.

(210) An insulator having a function of inhibiting passage of impurities such as water and hydrogen may be provided in contact with the inner wall of the opening in the insulator **274** and the insulator **280** in which the conductor **252** is embedded. As such an insulator, an insulator which can be used as the insulator **270** or the insulator **272**, such as aluminum oxide is preferably used, for example. Accordingly, impurities such as hydrogen and water can be inhibited from entering the oxide **230** through the conductor **252** from the insulator **280** or the like. Moreover, for example, the insulator can be deposited with good coverage by using an ALD method or a CVD method.

(211) Furthermore, conductors **256** functioning as wirings may be placed in contact with the top surface of the conductor **252**. A conductive material containing tungsten, copper, or aluminum as its main component is preferably used for the conductors **256** functioning as the wirings.

(212) [Capacitor **100**]

(213) As illustrated in FIG. **1**, the capacitor **100** shares some components with the transistor **200**. This embodiment shows an example in which at least part of the region **231b** provided in the oxide **230** of the transistor **200** functions as one electrode of the capacitor **100**.

(214) The capacitor **100** includes at least part of the region **231b** of the oxide **230**, the insulator **274** over the region **231**, and the conductor **130** over the insulator **274**. At least part of the conductor **130** is preferably placed over the insulator **274** to overlap with the region **231b**.

(215) At least the part of the region **231b** of the oxide **230** functions as one electrode of the capacitor **100** and the conductor **130** functions as the other electrode of the capacitor **100**. That is, the region **231b** functions as one of the source and the drain of the transistor **200** and as one electrode of the capacitor **100**. The insulator **274** functions as a dielectric of the capacitor **100**.

(216) The insulator **280** is preferably provided to cover the insulator **274** and the conductor **130**.

(217) For the conductor **130**, a conductive material containing tungsten, copper, or aluminum as its main component is preferably used. Moreover, although not illustrated, the conductor **130** may have a stacked-layer structure, and for example, may be a stack of titanium, titanium nitride, and the above-described conductive material.

(218) Furthermore, the conductor **252b** is in contact with the conductor **130** which is one electrode of the capacitor **100**. The conductor **252b** can be formed at the same time as the conductor **252a**, the conductor **252c**, and the conductor **252d**; thus, the process can be shortened.

(219) <Material for Semiconductor Device>

(220) Materials that can be used for a semiconductor device will be described below

(221) <<Substrate>>

(222) Examples of a substrate over which the transistor **200** is formed include an insulator substrate, a semiconductor substrate, and a conductor substrate. Examples of the insulator substrate include a glass substrate, a quartz substrate, a sapphire substrate, a stabilized zirconia substrate (an yttria-stabilized zirconia substrate or the like), and a resin substrate. Examples of the semiconductor substrate include a semiconductor substrate of silicon, germanium, or the like, and a compound semiconductor substrate of silicon carbide, silicon germanium, gallium arsenide, indium phosphide, zinc oxide, and gallium oxide. Moreover, a semiconductor substrate in which an insulator region is provided in the above semiconductor substrate, for example, an SOI (Silicon On

Insulator) substrate is given. Examples of the conductor substrate include a graphite substrate, a metal substrate, an alloy substrate, and a conductive resin substrate. In addition, a substrate including a metal nitride, a substrate including a metal oxide, or the like is given. Furthermore, a substrate which is an insulator substrate provided with a conductor or a semiconductor, a substrate which is a semiconductor substrate provided with a conductor or an insulator, a substrate which is a conductor substrate provided with a semiconductor or an insulator, or the like may be used. Alternatively, any of these substrates over which an element is provided may be used. Examples of the element provided over the substrate include a capacitor, a resistor, a switching element, a light-emitting element, and a memory element.

(223) Alternatively, a flexible substrate may be used as the substrate. Note that as a method for providing a transistor over a flexible substrate, there is a method in which the transistor is formed over a non-flexible substrate and then the transistor is separated and transferred to the substrate which is a flexible substrate. In that case, a separation layer is preferably provided between the non-flexible substrate and the transistor. The substrate may have elasticity. The substrate may have a property of returning to its original shape when bending or pulling is stopped. Alternatively, the substrate may have a property of not returning to its original shape. The substrate has a region with a thickness of, for example, greater than or equal to $5\text{ }\mu\text{m}$ and less than or equal to $700\text{ }\mu\text{m}$, preferably greater than or equal to $10\text{ }\mu\text{m}$ and less than or equal to $500\text{ }\mu\text{m}$, further preferably greater than or equal to $15\text{ }\mu\text{m}$ and less than or equal to $300\text{ }\mu\text{m}$. When the substrate has a small thickness, the weight of the semiconductor device including the transistor can be reduced. When the substrate has a small thickness, even in the case of using glass or the like, the substrate may have elasticity or a property of returning to its original shape when bending or pulling is stopped. Therefore, an impact or the like applied to the semiconductor device over the substrate due to dropping or the like can be reduced. That is, a durable semiconductor device can be provided.

(224) For the substrate which is a flexible substrate, metal, an alloy, resin, glass, or fiber thereof can be used, for example. As the substrate, a sheet, a film, a foil, or the like containing a fiber may be used. The substrate which is a flexible substrate preferably has a lower coefficient of linear expansion because deformation due to an environment is inhibited. For the substrate which is a flexible substrate, for example, a material whose coefficient of linear expansion is lower than or equal to $1 \times 10^{-3}/\text{K}$, lower than or equal to $5 \times 10^{-5}/\text{K}$, or lower than or equal to $1 \times 10^{-5}/\text{K}$ is used. Examples of the resin include polyester, polyolefin, polyamide (nylon, aramid, or the like), polyimide, polycarbonate, and acrylic. In particular, aramid is favorably used for the flexible substrate because of its low coefficient of linear expansion.

(225) <<Insulator>>

(226) Examples of an insulator include an insulating oxide, an insulating nitride, an insulating oxynitride, an insulating nitride oxide, an insulating metal oxide, an insulating metal oxynitride, and an insulating metal nitride oxide.

(227) Here, when a high-k material having a high relative permittivity is used for the insulator functioning as the gate insulator, miniaturization and high integration of the transistor can be achieved. In contrast, when a material having a low relative permittivity is used for the insulator functioning as an interlayer film, the parasitic capacitance generated between the wirings can be reduced. Therefore, a material is preferably selected depending on the function of an insulator.

(228) Moreover, examples of the insulator having a high relative permittivity include aluminum oxide, gallium oxide, hafnium oxide, zirconium oxide, an oxide containing aluminum and hafnium, an oxynitride containing aluminum and hafnium, an oxide containing silicon and hafnium, an oxynitride containing silicon and hafnium, and a nitride containing silicon and hafnium.

(229) Furthermore, examples of the insulator having a low relative permittivity include silicon oxide, silicon oxynitride, silicon nitride oxide, silicon nitride, silicon oxide to which fluorine is added, silicon oxide to which carbon is added, silicon oxide to which carbon and nitrogen are added, porous silicon oxide, and a resin.

(230) In particular, silicon oxide and silicon oxynitride are thermally stable. Accordingly, a stacked-layer structure which is thermally stable and has a low relative permittivity can be obtained by combination with a resin, for example. Examples of the resin include polyester, polyolefin, polyamide (nylon, aramid, or the like), polyimide, polycarbonate, and acrylic. Furthermore, combination of silicon oxide or silicon oxynitride with an insulator with a high relative permittivity allows the stacked-layer structure to be thermally stable and have a high relative permittivity, for example.

(231) In addition, when the transistor including an oxide semiconductor is surrounded by an insulator that has a function of inhibiting passage of oxygen and impurities such as hydrogen, the electrical characteristics of the transistor can be stabilized.

(232) As the insulator that has a function of inhibiting passage of oxygen and impurities such as hydrogen, for example, a single layer or stacked layers of an insulator containing boron, carbon, nitrogen, oxygen, fluorine, magnesium, aluminum, silicon, phosphorus, chlorine, argon, gallium, germanium, yttrium, zirconium, lanthanum, neodymium, hafnium, or tantalum is used. Specifically, as the insulator having a function of inhibiting passage of oxygen and impurities such as hydrogen, a metal oxide such as aluminum oxide, magnesium oxide, gallium oxide, germanium oxide, yttrium oxide, zirconium oxide, lanthanum oxide, neodymium oxide, hafnium oxide, or tantalum oxide, silicon nitride oxide, silicon nitride, or the like can be used.

(233) For example, an insulator that has a function of inhibiting passage of oxygen and impurities such as hydrogen is used as each of the insulator **222** and the insulator **210**. Note that an insulator containing oxides of one or both of aluminum and hafnium can be used as the insulator **222** and the insulator **210**. Aluminum oxide, hafnium oxide, an oxide containing aluminum and hafnium (hafnium aluminate), or the like is preferably used for the insulator containing oxides of one or both of aluminum and hafnium.

(234) As the insulator **220**, the insulator **224**, the insulator **250**, and the insulator **271**, for example, a single layer or stacked layers of an insulator containing boron, carbon, nitrogen, oxygen, fluorine, magnesium, aluminum, silicon, phosphorus, chlorine, argon, gallium, germanium, yttrium, zirconium, lanthanum, neodymium, hafnium, or tantalum are used. Specifically, the insulators preferably contain silicon oxide, silicon oxynitride, or silicon nitride.

(235) For example, when aluminum oxide, gallium oxide, hafnium aluminate, or hafnium oxide in each of the insulator **224** and the insulator **250** functioning as gate insulators, is in contact with the oxide **230**, entry of silicon in silicon oxide or silicon oxynitride into the oxide **230** can be inhibited. In contrast, when silicon oxide or silicon oxynitride in each of the insulator **224** and the insulator **250** is in contact with the oxide **230**, trap centers might be formed at the interface between aluminum oxide, gallium oxide, hafnium aluminate, or hafnium oxide and silicon oxide or silicon oxynitride. The trap centers can shift the threshold voltage of the transistor in the positive direction by trapping electrons in some cases.

(236) For the insulator **274** functioning as a dielectric, for example, silicon oxide, silicon oxynitride, silicon nitride oxide, silicon nitride, aluminum oxide, aluminum oxynitride, aluminum nitride oxide, aluminum nitride, hafnium oxide, hafnium oxynitride, hafnium nitride oxide, hafnium nitride, or hafnium aluminate is used, and the insulator is provided as stacked layers or a single layer. For example, a stacked-layer structure of a high-k material such as aluminum oxide and a material with high dielectric strength such as silicon oxynitride is preferably employed. With such a structure, the capacitor **100** can have sufficient capacitance owing to a high-k material and increased dielectric strength owing to a material with high dielectric strength; thus, the electrostatic breakdown of the capacitor **100** can be inhibited, which leads to improvement in the reliability of the capacitor **100**.

(237) The insulator **208**, the insulator **212**, the insulator **216**, and the insulator **280** preferably include an insulator with a low relative permittivity. For example, the insulator **208**, the insulator **212**, the insulator **216**, and the insulator **280** preferably include silicon oxide, silicon oxynitride,

silicon nitride oxide, silicon nitride, silicon oxide to which fluorine is added, silicon oxide to which carbon is added, silicon oxide to which carbon and nitrogen are added, porous silicon oxide, or a resin. Alternatively, the insulator **208**, the insulator **212**, the insulator **216**, and the insulator **280** preferably have a stacked-layer structure of a resin and silicon oxide, silicon oxynitride, silicon nitride oxide, silicon nitride, silicon oxide to which fluorine is added, silicon oxide to which carbon is added, silicon oxide to which carbon and nitrogen are added, or porous silicon oxide. Because silicon oxide and silicon oxynitride are thermally stable, combination of silicon oxide or silicon oxynitride with a resin allows the stacked-layer structure to be thermally stable and have a low relative permittivity. Examples of the resin include polyester, polyolefin, polyamide (nylon, aramid, or the like), polyimide, polycarbonate, and acrylic.

(238) As the insulator **270** and the insulator **272**, an insulator having a function of inhibiting passage of oxygen and impurities such as hydrogen is used. For the insulator **270** and the insulator **272**, a metal oxide such as aluminum oxide, hafnium oxide, hafnium aluminate, magnesium oxide, gallium oxide, germanium oxide, yttrium oxide, zirconium oxide, lanthanum oxide, neodymium oxide, or tantalum oxide; silicon nitride oxide; or silicon nitride may be used, for example.

(239) <<Conductor>>

(240) For the conductors, a material containing one or more kinds of metal elements selected from aluminum, chromium, copper, silver, gold, platinum, tantalum, nickel, titanium, molybdenum, tungsten, hafnium, vanadium, niobium, manganese, magnesium, zirconium, beryllium, indium, ruthenium, and the like can be used. Alternatively, a semiconductor having a high electric conductivity typified by polycrystalline silicon containing an impurity element such as phosphorus, or silicide such as nickel silicide may be used.

(241) Furthermore, a stack of a plurality of conductive layers formed with the above materials may be used. For example, a stacked-layer structure in which a material containing the above-described metal element and a conductive material containing oxygen are combined may be used.

Alternatively, a stacked-layer structure in which a material containing the above-described metal element and a conductive material containing nitrogen are combined may be used. Alternatively, a stacked-layer structure in which a material containing the above-described metal element, a conductive material containing oxygen, and a conductive material containing nitrogen are combined may be used.

(242) Note that when oxide is used for the channel formation region of the transistor, a stacked-layer structure in which a material containing the above-described metal element and a conductive material containing oxygen are combined is preferably used for the conductor functioning as the gate electrode. In this case, the conductive material containing oxygen is preferably formed on the channel formation region side. When the conductive material containing oxygen is provided on the channel formation region side, oxygen released from the conductive material is easily supplied to the channel formation region.

(243) It is particularly preferable to use a conductive material containing oxygen and a metal element in the metal oxide in which a channel is formed for the conductor functioning as the gate electrode. Moreover, a conductive material containing the above-described metal element and nitrogen may be used. For example, a conductive material containing nitrogen such as titanium nitride or tantalum nitride may be used. Indium tin oxide, indium oxide containing tungsten oxide, indium zinc oxide containing tungsten oxide, indium oxide containing titanium oxide, indium tin oxide containing titanium oxide, indium zinc oxide, or indium tin oxide to which silicon is added may be used. Indium gallium zinc oxide containing nitrogen may be used. By using such a material, hydrogen in the metal oxide in which a channel is formed can be trapped in some cases. Alternatively, hydrogen entering from an external insulator or the like can be trapped in some cases.

(244) For the conductor **260**, the conductor **205**, the conductor **203**, the conductor **207**, the conductor **209**, the conductor **130**, the conductor **252**, and the conductor **256**, a material containing

one or more kinds of metal elements selected from aluminum, chromium, copper, silver, gold, platinum, tantalum, nickel, titanium, molybdenum, tungsten, hafnium, vanadium, niobium, manganese, magnesium, zirconium, beryllium, indium, ruthenium, and the like can be used. Alternatively, a semiconductor having a high electric conductivity typified by polycrystalline silicon containing an impurity element such as phosphorus, or silicide such as nickel silicide may be used.

(245) <<Metal Oxide>>

(246) As the oxide **230**, a metal oxide functioning as an oxide semiconductor (hereinafter, also referred to as an oxide semiconductor) is preferably used. A metal oxide that can be used as the oxide **230** of the present invention will be described below.

(247) An oxide semiconductor preferably contains at least indium or zinc. In particular, indium and zinc are preferably contained. In addition, aluminum, gallium, yttrium, tin, or the like is preferably contained. Furthermore, one or more kinds selected from boron, silicon, titanium, iron, nickel, germanium, zirconium, molybdenum, lanthanum, cerium, neodymium, hafnium, tantalum, tungsten, magnesium, and the like may be contained.

(248) Here, the case where the oxide semiconductor is an In-M-Zn oxide that contains indium, an element M, and zinc is considered. Note that the element M is aluminum, gallium, yttrium, tin, or the like. Other elements that can be used as the element M include boron, silicon, titanium, iron, nickel, germanium, zirconium, molybdenum, lanthanum, cerium, neodymium, hafnium, tantalum, tungsten, and magnesium. Note that a plurality of elements described above may be combined as the element M.

(249) Note that in this specification and the like, a metal oxide containing nitrogen is also called a metal oxide in some cases. Alternatively, a metal oxide containing nitrogen may be called a metal oxynitride.

(250) Oxide semiconductors are classified into a single-crystal oxide semiconductor and a non-single-crystal oxide semiconductor. Examples of a non-single-crystal oxide semiconductor include a polycrystalline oxide semiconductor and an amorphous oxide semiconductor.

(251) As an oxide semiconductor used for a semiconductor of a transistor, a thin film having high crystallinity is preferably used. With the thin film, the stability or the reliability of the transistor can be improved. Examples of the thin film include a thin film of a single-crystal oxide semiconductor and a thin film of a polycrystalline oxide semiconductor. However, for forming the thin film of a single-crystal oxide semiconductor or the thin film of a polycrystalline oxide semiconductor over a substrate, high temperature or a laser heating process is needed. Thus, the manufacturing process cost is increased, and moreover, the throughput is decreased.

(252) Non-Patent Document 1 and Non-Patent Document 2 have reported that, in 2009, an In—Ga—Zn oxide having a CAAC structure (referred to as CAAC-IGZO) was found. Here, it has been reported that CAAC-IGZO has c-axis alignment, a grain boundary is not clearly observed, and CAAC-IGZO can be formed over a substrate at low temperatures. It has also been reported that a transistor including CAAC-IGZO has excellent electrical characteristics and reliability.

(253) In addition, in 2013, an In—Ga—Zn oxide having an nc structure (referred to as nc-IGZO) was found (see Non-Patent Document 3). Here, it has been reported that nc-IGZO has periodic atomic arrangement in a microscopic region (for example, a region with a size greater than or equal to 1 nm and less than or equal to 3 nm) and no regularity of crystal orientation is observed between different regions.

(254) Non-Patent Document 4 and Non-Patent Document 5 have shown a change in average crystal size due to irradiation of thin films of the above-described CAAC-IGZO with an electron beam, nc-IGZO, and IGZO having low crystallinity. In the thin film of IGZO having low crystallinity, crystalline IGZO with a thickness of approximately 1 nm was observed even before the electron beam irradiation. Thus, here, it has been reported that in IGZO, a completely amorphous structure could not be observed. In addition, it has been shown that the thin film of CAAC-IGZO and the

thin film of nc-IGZO each have higher stability against electron beam irradiation than the thin film of IGZO having low crystallinity. Thus, as the semiconductor of the transistor, the thin film of CAAC-IGZO or the thin film of nc-IGZO is preferably used.

(255) Non-Patent Document 6 discloses that a transistor including an oxide semiconductor has an extremely low leakage current in a non-conduction state; specifically, the off-state current per micrometer of the channel width of the transistor is in the order of $\text{yA}/\mu\text{m}$ ($10^{\text{sup.24}}$ $\text{A}/\mu\text{m}$). For example, a CPU with low-power consumption utilizing a characteristic of low leakage current of the transistor including an oxide semiconductor has been disclosed (see Non-Patent Document 7).

(256) Furthermore, the use of the transistor for the display device which utilizes a characteristic of low leakage current of the transistor including an oxide semiconductor has been reported (see Non-Patent Document 8). In the display device, a displayed image is changed several tens of times per second. The number of times an image is changed per second is called a refresh rate. The refresh rate is also referred to as driving frequency. Such high-speed screen switching that is hard for human eyes to recognize is considered as a cause of eye strain. Thus, it has been proposed that the refresh rate of a display device is lowered to reduce the number of image rewriting operations. Moreover, driving with a lowered refresh rate enables the power consumption of the display device to be reduced. Here, such a driving method is referred to as idling stop (IDS) driving.

(257) The discovery of the CAAC structure and the nc structure has contributed to an improvement in electrical characteristics and reliability of the transistor including an oxide semiconductor having the CAAC structure or the nc structure, a reduction in manufacturing process cost, and an improvement in throughput. Furthermore, studies of applications of the transistor to the display device and LSI utilizing a characteristic of low leakage current of the transistor have been developed.

(258) [Composition of Metal Oxide]

(259) Described below is the composition of a CAC (Cloud-Aligned Composite)-OS applicable to a transistor disclosed in one embodiment of the present invention.

(260) Note that in this specification and the like, CAAC (c-axis aligned crystal) and CAC (Cloud-Aligned Composite) might be stated. Note that CAAC refers to an example of a crystal structure, and CAC refers to an example of a function or a material composition.

(261) A CAC-OS or a CAC-metal oxide has a conducting function in a part of the material and has an insulating function in another part of the material, and has a function of a semiconductor as the whole material. Note that in the case where the CAC-OS or the CAC-metal oxide is used in an active layer of a transistor, the conducting function is a function of allowing electrons (or holes) serving as carriers to flow, and the insulating function is a function of not allowing electrons serving as carriers to flow. By the complementary action of the conducting function and the insulating function, the CAC-OS or the CAC-metal oxide can have a switching function (On/Off function). In the CAC-OS or the CAC-metal oxide, separation of the functions can maximize each function.

(262) Furthermore, the CAC-OS or the CAC-metal oxide includes conductive regions and insulating regions. The conductive regions have the above-described conducting function, and the insulating regions have the above-described insulating function. In some cases, the conductive regions and the insulating regions in the material are separated at the nanoparticle level. In some cases, the conductive regions and the insulating regions are unevenly distributed in the material. The conductive regions are observed to be coupled in a cloud-like manner with their boundaries blurred, in some cases.

(263) Furthermore, in the CAC-OS or the CAC-metal oxide, the conductive regions and the insulating regions each have a size of greater than or equal to 0.5 nm and less than or equal to 10 nm, preferably greater than or equal to 0.5 nm and less than or equal to 3 nm and are dispersed in the material, in some cases.

(264) Moreover, the CAC-OS or the CAC-metal oxide includes components having different

bandgaps. For example, the CAC-OS or the CAC-metal oxide includes a component having a wide gap due to the insulating region and a component having a narrow gap due to the conductive region.

(265) When carriers flow in this composition, carriers mainly flow in the component having a narrow gap. The component having a narrow gap complements the component having a wide gap, and carriers also flow in the component having a wide gap in conjunction with the component having a narrow gap. Therefore, in the case where the above-described CAC-OS or CAC-metal oxide is used in a channel formation region of a transistor, high current drive capability in the on state of the transistor, that is, a high on-state current and high field-effect mobility, can be obtained.

(266) In other words, the CAC-OS or the CAC-metal oxide can also be called a matrix composite or a metal matrix composite.

(267) [Structure of Metal Oxide]

(268) Oxide semiconductors are classified into a single crystal oxide semiconductor and a non-single-crystal oxide semiconductor. Examples of a non-single-crystal oxide semiconductor include a CAAC-OS (c-axis aligned crystalline oxide semiconductor), a polycrystalline oxide semiconductor, an nc-OS (nanocrystalline oxide semiconductor), an amorphous-like oxide semiconductor (a-like OS), and an amorphous oxide semiconductor.

(269) The CAAC-OS has c-axis alignment, its nanocrystals are connected in the a-b plane direction, and its crystal structure has distortion. Note that distortion refers to a portion where the direction of a lattice arrangement changes between a region with a uniform lattice arrangement and another region with a uniform lattice arrangement in a region where the plurality of nanocrystals are connected.

(270) The nanocrystal is basically a hexagon but is not always a regular hexagon and is a non-regular hexagon in some cases. A pentagonal lattice arrangement, a heptagonal lattice arrangement, and the like are included in the distortion in some cases. Note that a clear crystal grain boundary (also referred to as a grain boundary) cannot be observed even in the vicinity of distortion in the CAAC-OS. That is, formation of a crystal grain boundary is inhibited by the distortion of a lattice arrangement. This is probably because the CAAC-OS can tolerate distortion owing to a low density of oxygen atom arrangement in the a-b plane direction, a change in interatomic bond distance by substitution of a metal element, and the like.

(271) In addition, the CAAC-OS tends to have a layered crystal structure (also referred to as a layered structure) in which a layer containing indium and oxygen (hereinafter, In layer) and a layer containing the element M, zinc, and oxygen (hereinafter, (M, Zn) layer) are stacked. Note that indium and the element M can be replaced with each other, and when the element M of the (M, Zn) layer is replaced by indium, the layer can also be represented as an (In, M, Zn) layer. When indium of the In layer is replaced by the element M, the layer can also be represented as an (In, M) layer.

(272) The CAAC-OS is an oxide semiconductor having high crystallinity. In contrast, it can be said that in the CAAC-OS, a reduction in electron mobility due to the crystal grain boundary is less likely to occur because a clear crystal grain boundary cannot be observed. Since the crystallinity of an oxide semiconductor might be decreased due to entry of impurities, formation of defects, or the like, it can be said that the CAAC-OS is an oxide semiconductor that has small amounts of impurities and defects (oxygen vacancies or the like). Thus, an oxide semiconductor including a CAAC-OS is physically stable. Therefore, the oxide semiconductor including a CAAC-OS is resistant to heat and has high reliability.

(273) In the nc-OS, a microscopic region (for example, a region with a size greater than or equal to 1 nm and less than or equal to 10 nm, in particular, a region with a size greater than or equal to 1 nm and less than or equal to 3 nm) has a periodic atomic arrangement. There is no regularity of crystal orientation between different nanocrystals in the nc-OS. Thus, the orientation of the whole film is not observed. Accordingly, in some cases, the nc-OS cannot be distinguished from an a-like OS or an amorphous oxide semiconductor depending on an analysis method.

(274) The a-like OS is an oxide semiconductor that has a structure intermediate between those of the nc-OS and the amorphous oxide semiconductor. The a-like OS has a void or a low-density region. That is, the a-like OS has low crystallinity as compared with the nc-OS and the CAAC-OS. (275) Oxide semiconductors have various structures with different properties. Two or more kinds of the amorphous oxide semiconductor, the polycrystalline oxide semiconductor, the a-like OS, the nc-OS, and the CAAC-OS may be included in an oxide semiconductor of one embodiment of the present invention.

(276) [Transistor Including Oxide Semiconductor]

(277) Next, the case where the oxide semiconductor is used for a transistor will be described.

(278) Note that when the oxide semiconductor is used for a transistor, the transistor can have high field-effect mobility. In addition, a transistor with high reliability can be achieved.

(279) Moreover, an oxide semiconductor with low carrier density is preferably used for the transistor. In the case where the carrier density of an oxide semiconductor film is reduced, the concentration of impurities in the oxide semiconductor film is reduced so that the density of defect states is reduced. In this specification and the like, a state with a low impurity concentration and a low density of defect states is referred to as a highly purified intrinsic or substantially highly purified intrinsic. The oxide semiconductor has, for example, a carrier density lower than $8 \times 10^{11}/\text{cm}^3$, preferably lower than $1 \times 10^{11}/\text{cm}^3$, and further preferably lower than $1 \times 10^{10}/\text{cm}^3$, and higher than or equal to $1 \times 10^{-9}/\text{cm}^3$.

(280) Furthermore, a highly purified intrinsic or substantially highly purified intrinsic oxide semiconductor film has a low density of defect states and accordingly has a low density of trap states in some cases.

(281) In addition, charges trapped by the trap states in the oxide semiconductor take a long time to disappear and may behave like fixed charges. Thus, a transistor whose channel is formed in the oxide semiconductor having a high density of trap states has unstable electrical characteristics in some cases.

(282) Thus, in order to stabilize electrical characteristics of the transistor, it is effective to reduce the concentration of impurities in the oxide semiconductor. In addition, in order to reduce the concentration of impurities in the oxide semiconductor, the concentration of impurities in an adjacent film is also preferably reduced. Examples of the impurities include hydrogen, nitrogen, alkali metal, alkaline earth metal, iron, nickel, and silicon.

(283) [Impurity]

(284) Here, the influence of impurities in the oxide semiconductor will be described.

(285) When silicon or carbon that is one of Group 14 elements is contained in the oxide semiconductor, defect states are formed in the oxide semiconductor. Thus, the concentration of silicon or carbon in the oxide semiconductor and the concentration of silicon or carbon in the vicinity of an interface with the oxide semiconductor (the concentration obtained by secondary ion mass spectrometry (SIMS)) is set to be lower than or equal to 2×10^{18} atoms/ cm^3 , preferably lower than or equal to 2×10^{17} atoms/ cm^3 .

(286) When the oxide semiconductor contains an alkali metal or an alkaline earth metal, defect states are formed and carriers are generated, in some cases. Thus, a transistor including an oxide semiconductor that contains an alkali metal or an alkaline earth metal is likely to have normally-on characteristics. Therefore, it is preferable to reduce the concentration of an alkali metal or an alkaline earth metal in the oxide semiconductor. Specifically, the concentration of alkali metal or alkaline earth metal in the oxide semiconductor, which is measured by SIMS, is lower than or equal to 1×10^{18} atoms/ cm^3 , preferably lower than or equal to 2×10^{16} atoms/ cm^3 .

(287) Furthermore, when the oxide semiconductor contains nitrogen, the oxide semiconductor easily becomes n-type by generation of electrons serving as carriers and an increase in carrier density. As a result, a transistor including an oxide semiconductor that contains nitrogen as a semiconductor is likely to have normally-on characteristics. For this reason, nitrogen in the oxide

semiconductor is preferably reduced as much as possible. For example, the concentration of nitrogen in the oxide semiconductor measured by SIMS is set to lower than 5×10^{19} atoms/cm³, preferably lower than or equal to 5×10^{18} atoms/cm³, further preferably lower than or equal to 1×10^{18} atoms/cm³, and still further preferably lower than or equal to 5×10^{17} atoms/cm³.

(288) Hydrogen in an oxide semiconductor reacts with oxygen bonded to a metal atom to be water, and thus causes an oxygen vacancy, in some cases. Entry of hydrogen into the oxygen vacancy generates an electron serving as a carrier in some cases. Furthermore, in some cases, bonding of part of hydrogen to oxygen bonded to a metal atom causes generation of an electron serving as a carrier. Accordingly, a transistor including an oxide semiconductor that contains hydrogen is likely to have normally-on characteristics. For this reason, hydrogen in the oxide semiconductor is preferably reduced as much as possible. Specifically, the hydrogen concentration of the oxide semiconductor measured by SIMS is lower than 1×10^{20} atoms/cm³, preferably lower than 1×10^{19} atoms/cm³, further preferably lower than 5×10^{18} atoms/cm³, and still further preferably lower than 1×10^{18} atoms/cm³.

(289) When an oxide semiconductor with sufficiently reduced impurities is used for a channel formation region of a transistor, the transistor can have stable electrical characteristics.

(290) <Structure Example 2 of Semiconductor Device>

(291) An example of a semiconductor device of one embodiment of the present invention is described below with reference to FIG. 4.

(292) FIG. 4(A) is a top view of a transistor **201**. Furthermore, FIGS. 4(B), 4(C), and 4(D) are cross-sectional views of the transistor **201**. Here, FIG. 4(B) is a cross-sectional view of a portion denoted by dashed-dotted line A-B in FIG. 4(A), and is also a cross-sectional view of the transistor **200** in the channel length direction. FIG. 4(C) is a cross-sectional view of a portion denoted by dashed-dotted line C-D in FIG. 4(A), and is also a cross-sectional view of the transistor **200** in the channel width direction. FIG. 4(D) is a cross-sectional view of a portion denoted by dashed-dotted line E-F in FIG. 4(A), and is also a cross-sectional view illustrating a connection portion between the oxide **230** and the conductor **203** and a connection portion between the conductor **252b** and the oxide **230**. For simplification of the drawing, some components are omitted in the top view in FIG. 4(A).

(293) Note that in the semiconductor device illustrated in FIG. 4, components having the same functions as the components included in the semiconductor device described in <Structure example 1 of semiconductor device> are denoted by the same reference numerals.

(294) A structure of the transistor **201** will be described with reference to FIG. 4 below. Note that also in this section, the materials described in detail in <Structure example 1 of semiconductor device> can be used as materials of the transistor **201**.

(295) In the transistor **201**, a conductor **285** functioning as a source electrode or a drain electrode is provided over the oxide **230b**. An insulator **286** is provided over the conductor **285**. For the conductor **285**, a material similar to that for the conductor **203**, the conductor **205**, or the conductor **260** can be used. It is particularly preferable to use tantalum nitride or tungsten for the conductor **285**. For the insulator **286**, a material similar to that for the insulator **270** or the insulator **272** can be used. By provision of the insulator **286**, oxidation of the conductor **285** can be inhibited, and an increase in the electrical resistance of the conductor **285** can be inhibited. In particular, aluminum oxide is preferably used for the insulator **286**. In addition, although the channel length of the transistor **201** is determined depending on the length between the conductors **285**, a problem in that the channel length of the transistor **201** becomes unintentionally long might be caused due to oxidation of end portions of the conductors **285** facing each other. The insulator **286** is preferably provided in order to prevent such a defect.

(296) As illustrated in FIG. 4(B), a region of the oxide **230b** that is in contact with the conductor **285** and indicated by a dotted line becomes an n-type low-resistance region. This is probably

because the conductor **285** extracts oxygen in the oxide **230b** and generates an oxygen vacancy in the oxide **230b**. Impurities existing inside or outside the oxide **230b** are trapped by the oxygen vacancy in the oxide **230b**, and the resistance of the region is reduced.

(297) The low-resistance region of the oxide **230b** is electrically connected to the conductor **203** through the opening provided in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**.

(298) The oxide **230c**, an oxide **230d**, the insulator **250**, the conductor **260**, and the insulator **270** are provided to cover part of the oxide **230b**, part of the conductor **285**, and part of the insulator **286**. Note that the width in the A-B direction and the length in the C-D direction of the conductor **260** are less than those of the oxide **230c**, the oxide **230d**, the insulator **250**, and the insulator **270** as illustrated in FIG. 4(A), FIG. 4(B), and FIG. 4(C). Thus, the insulator **270** covers the top surface and the side surface of the insulator **250** and is in contact with the insulator **250** outside the conductor **260**. Since a material that inhibits passage of oxygen is used for the insulator **270**, oxidation of the conductor **260** is inhibited owing to the insulator **270** provided in such a manner, so that an increase in the electrical resistance can be inhibited.

(299) A material similar to that for the oxide **230b** can be used for the oxide **230c**. A material similar to that for the oxide **230c** can be used for the oxide **230d**. Note that the oxide **230c** is not necessarily formed.

(300) In the transistor **201**, a channel is formed in a region interposed between the pair of conductors **285** or the pair of low-resistance regions of the oxide **230b** and the oxide **230c**.

(301) An insulator **287** and an insulator **288** are formed over the insulator **280**. For the insulator **287**, an oxide insulator that is deposited by a sputtering method is preferably used, and for example, aluminum oxide, hafnium oxide, or hafnium aluminate is preferably used. With such an insulator **287**, oxygen can be added to the insulator **280** through a surface of the insulator **280** that is in contact with the insulator **287**, so that the insulator **280** can be in an oxygen excess state. Oxygen that has been supplied to the insulator **280** is supplied to the oxide **230**.

(302) Furthermore, when an insulating material that is less likely to pass oxygen, such as aluminum oxide, hafnium oxide, or hafnium aluminate is used for the insulator **287**, oxygen added to the insulator **224** and the insulator **280** can be inhibited from being diffused upward during the deposition. Accordingly, oxygen can be added to the insulator **280** further efficiently.

(303) A material similar to that for the insulator **208**, the insulator **216**, and the insulator **280** can be used for the insulator **288**.

(304) As illustrated in FIG. 4(B), FIG. 4(C), and FIG. 4(D), an opening is provided in insulators such as the insulator **280**, the insulator **287**, and the insulator **288**, and the conductor **252** (the conductor **252a**, the conductor **252b**, the conductor **252c**, and the conductor **252d**) is provided in the opening. An insulator **289** is provided between the conductor **252** and the insulators such as the insulator **280**, the insulator **287**, and the insulator **288**. A material similar to that for the insulator **270** can be used for the insulator **289**, whereby entry of impurities from the insulator **280** and an insulator or a conductor thereover to the oxide **230** is inhibited.

(305) Here, it is preferable that the conductor **252a** be electrically connected to the oxide **230** by being not only in contact with the conductor **285** over the oxide **230** but also in contact with the side surface of the oxide **230**. It is particularly preferable that the conductor **252a** be in contact with one or both of the side surface on the C side and the side surface on the D side, which intersect with the channel width direction of the oxide **230**. Moreover, the conductor **252a** may be in contact with the side surface on the A side, which intersects with the channel length direction of the oxide **230**. When the conductor **252a** is in contact with the side surface of the oxide **230** in addition to the conductor **285** as described above, the contact area of the contact portion of the conductor **252a** and the oxide **230** can be increased without an increase in the area of the top surface of the contact portion, so that the contact resistance between the conductor **252a** and the oxide **230** can be reduced. Accordingly, miniaturization of the source electrode and the drain electrode of the

transistor can be achieved and, in addition, the on-state current can be increased.

(306) FIG. 4(D) illustrates a cross section of a connection portion between the oxide **230** and the conductor **203** and a connection portion between the conductor **252b** and the oxide **230**. The oxide **230b** is electrically connected to the conductor **203** through the opening provided in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**. Note that like the above-described conductor **252a**, the conductor **252b** may be in contact with not only a top surface of the conductor **285** but also the side surface of the oxide **230**.

(307) As illustrated in FIG. 4(A) and FIG. 4(D), in order to cover the opening formed in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**, the oxide **230a** and the oxide **230b** are each preferably formed to have a wider width in the E-F direction than the opening in the region overlapping with the opening. Therefore, the widths of the oxide **230a** and the oxide **230b** in the E-F direction in that region may be wider than the widths of the oxide **230a** and the oxide **230b** in the C-D direction in a region where a channel is formed or a region on the A side. With such a structure, contact between the oxide **230b** and the conductor **203** can be assured.

(308) <Method for Manufacturing Transistor>

(309) Next, a method for manufacturing a semiconductor device including the transistor **200** of the present invention will be described with reference to FIG. 5 to FIG. 22. In FIG. 5 to FIG. 22, (A) of each drawing is a top view. Moreover, (B) of each drawing is a cross-sectional view corresponding to a portion denoted by dashed-dotted line A-B in (A). Furthermore, (C) of each drawing is a cross-sectional view corresponding to a portion denoted by dashed-dotted line C-D in (A). Furthermore, (D) of each drawing is a cross-sectional view corresponding to a portion denoted by dashed-dotted line E-F in (A).

(310) First, a substrate (not illustrated) is prepared, and the insulator **208** is deposited over the substrate. The insulator **208** can be deposited by a sputtering method, a chemical vapor deposition (CVD) method, a molecular beam epitaxy (MBE) method, a pulsed laser deposition (PLD) method, an ALD (Atomic Layer Deposition) method, or the like.

(311) Note that CVD methods can be classified into a plasma enhanced CVD (PECVD) method using plasma, a thermal CVD (TCVD) method using heat, a photo CVD method using light, and the like. Moreover, the CVD methods can be classified into a metal CVD (MCVD) method and a metal organic CVD (MOCVD) method depending on a source gas.

(312) The PECVD method is a deposition method that can provide a high-quality film at a relatively low temperature. Furthermore, a thermal CVD method does not use plasma and thus can reduce plasma damage to an object. For example, a wiring, an electrode, or an element (a transistor, a capacitor, or the like) included in a semiconductor device might be charged up by receiving charges from plasma. In that case, accumulated charges might break the wiring, electrode, element, or the like included in the semiconductor device. In contrast, in the case of a thermal CVD method not using plasma, such plasma damage is not caused and the yield of the semiconductor device can be increased. A thermal CVD method does not cause plasma damage during deposition, so that a film with few defects can be obtained.

(313) An ALD method is also a deposition method that can reduce plasma damage to an object. Also an ALD method does not cause plasma damage during deposition, so that a film with few defects can be obtained.

(314) Unlike a deposition method in which particles ejected from a target or the like are deposited, a CVD method and an ALD method are deposition methods in which a film is formed by reaction at a surface of an object. Thus, a CVD method and an ALD method are deposition methods which are less likely to be influenced by the shape of an object and enable favorable step coverage. In particular, an ALD method enables excellent step coverage and excellent thickness uniformity and can be favorably used for covering a surface of an opening portion with a high aspect ratio, for example. On the other hand, an ALD method has a relatively low deposition rate; thus, it is sometimes preferable to combine an ALD method with another deposition method with a high

deposition rate such as a CVD method.

(315) By a CVD method or an ALD method, composition of a film to be obtained can be controlled with a flow rate ratio of the source gases. For example, by a CVD method or an ALD method, a film with a certain composition can be deposited depending on a flow rate ratio of the source gases. Moreover, in a CVD method or an ALD method, by changing the flow rate ratio of the source gases while depositing the film, a film whose composition is continuously changed can be deposited, for example. In the case where the film is deposited while changing the flow rate ratio of the source gases, as compared to the case where the film is deposited using a plurality of deposition chambers, time taken for the deposition can be shortened because time taken for transfer and pressure adjustment is omitted. Thus, the productivity of semiconductor devices can be improved in some cases.

(316) In this embodiment, as the insulator **208**, silicon oxide is deposited by a CVD method.

(317) Next, the insulator **210** is formed over the insulator **208**. In this embodiment, aluminum oxide is deposited as the insulator **210** by a sputtering method. The insulator **210** may have a multilayer structure. For example, aluminum oxide may be deposited by a sputtering method and aluminum oxide may be deposited over the aluminum oxide by an ALD method. Alternatively, aluminum oxide may be deposited by an ALD method and aluminum oxide may be deposited over the aluminum oxide by a sputtering method.

(318) Next, a conductive film **203A** and a conductive film **203B** are sequentially deposited over the insulator **210**. The conductive film **203A** and the conductive film **203B** can be formed by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. In this embodiment, tungsten is deposited by a sputtering method as the conductive film **203A** and titanium nitride is deposited by a sputtering method as the conductive film **203B**. Note that as the conductive film **203A**, a conductor such as aluminum or copper can be used as well as tungsten. A material that has a higher oxidation resistance (that is less likely to be oxidized) than the conductive film **203A** is preferably used for the conductive film **203B**, and a metal nitride can be used, for example. As the metal nitride, tantalum nitride or the like can be used as well as titanium nitride.

(319) Next, masks **262** are formed over the conductive film **203B** by a lithography method (see FIG. 5).

(320) Note that in the lithography method, first, a resist is exposed to light through a mask. Next, a region exposed to light is removed or left using a developing solution, so that a resist mask is formed. Then, etching treatment is performed through the resist mask, whereby a conductor, a semiconductor, an insulator, or the like can be processed into a desired shape. The resist mask is formed by, for example, exposure of the resist to light using KrF excimer laser light, ArF excimer laser light, or EUV (Extreme Ultraviolet) light. Alternatively, a liquid immersion technique may be employed in which a portion between a substrate and a projection lens is filled with liquid (for example, water) to perform light exposure. An electron beam or an ion beam may be used instead of the above-described light. Note that a mask is not necessary in the case of using an electron beam or an ion beam. To remove the resist mask, dry etching treatment such as ashing or wet etching treatment can be performed, wet etching treatment can be performed after dry etching treatment, or dry etching treatment can be performed after wet etching treatment.

(321) A hard mask formed of an insulator or a conductor may be used instead of the resist mask. In the case where a hard mask is used, a hard mask with a desired shape can be formed by forming an insulating film or a conductive film to be the material of the hard mask over the conductive film **203B**, forming a resist mask thereover, and then etching the material of the hard mask.

(322) Then, the conductive film **203A** and the conductive film **203B** are processed using the masks **262** to form the conductor **203** including the conductor **203a** and the conductor **203b** over the conductor **203a**, and the conductor **205** including the conductor **205a** and the conductor **205b** over the conductor **205a** (see FIG. 6).

(323) For the processing, a dry etching method or a wet etching method can be employed. A

processing employing a dry etching method is suitable for microfabrication.

(324) As a dry etching apparatus, a capacitively coupled plasma (CCP) etching apparatus including parallel plate type electrodes can be used. The capacitively coupled plasma etching apparatus including the parallel plate type electrodes may have a structure in which a high-frequency power is applied to one of the parallel plate type electrodes. Alternatively, a structure in which different high-frequency powers are applied to one of the parallel plate type electrodes may be employed. Alternatively, a structure in which high-frequency powers with the same frequency are applied to the parallel plate type electrodes may be employed. Alternatively, a structure in which high-frequency powers with different frequencies are applied to the parallel plate type electrodes may be employed. Alternatively, a dry etching apparatus including a high-density plasma source can be used. As the dry etching apparatus including a high-density plasma source, an inductively coupled plasma (ICP) etching apparatus can be used, for example.

(325) In the case where a hard mask is used for etching of the conductive film **203A** and the conductive film **203B**, the etching treatment may be performed after the resist mask used for formation of the hard mask is removed or may be performed while the resist mask remains. In the latter case, the resist mask is removed during the etching in some cases. The hard mask may be removed by etching after the etching of the conductive film. In contrast, the hard mask does not need to be removed in the case where the hard mask material does not affect the following process or can be utilized in the following process.

(326) Next, an insulating film **216A** is formed over the insulator **210**, the conductor **203**, and the conductor **205** (see FIG. 7). The insulating film **216A** can be formed by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. In this embodiment, as the insulating film **216A**, silicon oxide is formed by a CVD method.

(327) Next, part of the insulating film **216A** is removed by CMP treatment, so that the conductor **203** and the conductor **205** are exposed. As a result, the insulator **216** remains between the conductor **203** and the conductor **205** and around these conductors. In this way, the insulator **216**, the conductor **203**, and the conductor **205** with flat top surfaces can be formed (see FIG. 8). Note that by the CMP treatment, the conductor **203b** and the conductor **205b** are partly removed in some cases.

(328) Next, the insulator **220** is deposited over the insulator **216**, the conductor **203**, and the conductor **205**. The insulator **220** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(329) Then, the insulator **222** is deposited over the insulator **220**. The insulator **222** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(330) In particular, an insulator containing oxides of one or both of aluminum and hafnium is preferably used as the insulator **222**. Aluminum oxide, hafnium oxide, an oxide containing aluminum and hafnium (hafnium aluminate), or the like is preferably used for the insulator containing oxides of one or both of aluminum and hafnium. The insulator **222** is preferably formed by an ALD method. The insulator **222** deposited by an ALD method has a barrier property against oxygen, hydrogen, and water. When the insulator **222** has a barrier property against hydrogen and water, hydrogen and water in structure bodies provided around the transistor **200** are not diffused into the transistor **200**, and generation of oxygen vacancies in the oxide **230** can be inhibited.

(331) Then, the insulator **224** is deposited over the insulator **222**. The insulator **224** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like (see FIG. 9).

(332) Subsequently, heat treatment is preferably performed. The heat treatment is performed at a temperature higher than or equal to 250° C. and lower than or equal to 650° C., preferably higher than or equal to 300° C. and lower than or equal to 500° C., and further preferably higher than or equal to 320° C. and lower than or equal to 450° C. The first heat treatment is performed in a

nitrogen atmosphere, an inert gas atmosphere, or an atmosphere containing an oxidizing gas at 10 ppm or more, 1% or more, or 10% or more. The first heat treatment may be performed under a reduced pressure. Alternatively, the first heat treatment may be performed by performing heat treatment in a nitrogen atmosphere or an inert gas atmosphere, and then performing heat treatment in an atmosphere containing an oxidizing gas at 10 ppm or more, 1% or more, or 10% or more in order to compensate for released oxygen.

(333) By the above heat treatment, impurities such as hydrogen and water in the insulator **224** can be removed, for example.

(334) Alternatively, as the heat treatment, plasma treatment using oxygen may be performed under a reduced pressure. For the plasma treatment using oxygen, an apparatus including a power source for generating high-density plasma using microwaves is preferably used, for example.

Alternatively, a power source for applying an RF (Radio Frequency) to a substrate side may be included. The use of high-density plasma enables high-density oxygen radicals to be generated, and application of the RF to the substrate side allows oxygen radicals generated by the high-density plasma to be efficiently introduced into the insulator **224**. Alternatively, after plasma treatment using an inert gas is performed with this apparatus, plasma treatment using oxygen may be performed to compensate for released oxygen. Note that first heat treatment is not necessarily performed in some cases.

(335) This heat treatment can also be performed after deposition of the insulator **220** and after deposition of the insulator **222**. Although the heat treatment can be performed under the above-described heat treatment conditions, heat treatment after deposition of the insulator **220** is preferably performed in an atmosphere containing nitrogen.

(336) In this embodiment, as the heat treatment, treatment is performed in a nitrogen atmosphere at 400° C. for one hour after deposition of the insulator **224**.

(337) Next, an oxide film **230A** to be the oxide **230a** is formed over the insulator **224**.

(338) The oxide film **230A** can be formed by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(339) In the case where the oxide film **230A** is formed by a sputtering method, for example, oxygen or a mixed gas of oxygen and a rare gas is used as a sputtering gas. By increasing the proportion of oxygen in the sputtering gas, the amount of excess oxygen in the oxide film to be deposited can be increased. In the case where the oxide film is formed by a sputtering method, the above-described In-M-Zn oxide target can be used.

(340) In particular, part of oxygen in the sputtering gas is supplied to the insulator **224** in some cases, at the formation of the oxide film **230A**. Note that the proportion of oxygen in the sputtering gas for the oxide film **230A** is higher than or equal to 70%, preferably higher than or equal to 80%, and further preferably 100%.

(341) In this embodiment, the oxide film **230A** is formed using a target of In:Ga:Zn=1:3:4 [atomic ratio] by a sputtering method. Note that the oxide film is preferably formed by appropriate selection of deposition conditions and an atomic ratio to have characteristics required for the oxide **230**.

(342) Next, an opening reaching the conductor **203** is formed in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide film **230A** by a lithography method. First, a mask **263** is formed over the oxide film **230A** (see FIG. 9). The mask **263** used for forming the opening may be a resist mask or a hard mask.

(343) Next, the insulator **220**, the insulator **222**, the insulator **224**, and the oxide film **230A** are processed using the mask **263** to expose the surface of the conductor **203**, so that the opening is formed (see FIG. 10). For the processing, a dry etching method or a wet etching method can be used. A dry etching method is suitable for microfabrication. Note that the insulator **220**, the insulator **222**, and the insulator **224** are processed through the oxide film **230A**. Specifically, when the surface of the conductor **203** is partly exposed, a mask formed of a resist mask, a hard mask, or the like is formed over the oxide film **230A**, and then the insulator **220**, the insulator **222**, the

insulator **224**, and the oxide film **230A** are processed. In other words, the mask is not formed on a surface of the insulator (the insulator **220**, the insulator **222**, and the insulator **224**) functioning as the gate insulating film. Therefore, the mask is not attached to the surface of the insulator functioning as the gate insulating film; thus, the gate insulating film can be prevented from being contaminated and damaged by an impurity in the resist mask and the like, a component in the hard mask, and components in plasma and a chemical solution used for removal of the mask. Through such a process, a method for manufacturing a highly reliable semiconductor device can be provided.

(344) Next, an oxide film **230B** is formed over the oxide film **230A** (see FIG. **11**). At this time, the oxide film **230B** is also formed in the opening and electrically connected to the conductor **203** through the opening. When the oxide **230b** is connected to the conductor **203** without through the oxide **230a**, the series resistance and the contact resistance can be reduced. With such a structure, a semiconductor device with favorable electrical characteristics can be obtained. More specifically, a transistor with an increased on-state current and a semiconductor device including the transistor can be obtained.

(345) The oxide film **230B** can be formed by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(346) In the case where the oxide film **230B** is formed by a sputtering method, for example, oxygen or a mixed gas of oxygen and a rare gas is used as a sputtering gas. By increasing the proportion of oxygen in the sputtering gas, the amount of excess oxygen in the oxide film to be deposited can be increased. In the case where the oxide film is formed by a sputtering method, the above-described In-M-Zn oxide target can be used.

(347) In the case where the oxide film **230B** is formed by a sputtering method and the proportion of oxygen in the sputtering gas is higher than or equal to 1% and lower than or equal to 30%, preferably higher than or equal to 5% and lower than or equal to 20%, an oxygen-deficient oxide semiconductor is formed. A transistor including an oxygen-deficient oxide semiconductor can have relatively high field-effect mobility.

(348) In this embodiment, the oxide film **230B** is deposited using a target of In:Ga:Zn=4:2:4.1 [atomic ratio] by a sputtering method. Note that the oxide film is preferably formed by appropriate selection of deposition conditions and an atomic ratio to have characteristics required for the oxide **230**.

(349) Next, heat treatment may be performed. For the heat treatment, the above-described heat treatment conditions can be used. By the heat treatment, impurities such as water and hydrogen in the oxide film **230A** and the oxide film **230B** can be removed, for example. In this embodiment, treatment is performed in a nitrogen atmosphere at 400° C. for one hour, and treatment is successively performed in an oxygen atmosphere at 400° C. for one hour.

(350) Then, the oxide film **230A** and the oxide film **230B** are processed into island shapes to form the oxide **230a** and the oxide **230b** (see FIG. **12**).

(351) As illustrated in FIG. **12(A)** and FIG. **12(D)**, the oxide **230a** and the oxide **230b** are each preferably formed to have a wider width in the E-F direction than the opening in the region overlapping with the opening formed in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**. Therefore, the widths of the oxide **230a** and the oxide **230b** in the E-F direction in that region may be wider than the widths of the oxide **230a** and the oxide **230b** in the C-D direction in a region where a channel is formed or a region on the A side. With such a structure, contact between the oxide **230b** and the conductor **203** can be assured. Furthermore, the area of the capacitor **100** can be increased, and an increase in the capacity of the capacitor **100** can be expected.

(352) Note that in the above step, the insulator **224** may be processed into an island shape. Furthermore, the insulator **224** may be subjected to half-etching. In the case where the insulator **224** is subjected to half-etching, the insulator **224** remains also under the oxide **230c** to be formed

in a later step. Note that the insulator **224** can be processed into an island shape when an insulating film **272A** is processed in a later step. In this case, the insulator **222** may be used as an etching stopper film.

(353) Here, the oxide **230a** and the oxide **230b** are formed to at least partly overlap with the conductor **205**. It is preferable that side surfaces of the oxide **230a** and the oxide **230b** be substantially perpendicular to the insulator **222**. When the side surfaces of the oxide **230a** and the oxide **230b** are substantially perpendicular to the insulator **222**, a plurality of transistors **200** can be provided in a small area with high density. Note that an angle formed by the side surfaces of the oxide **230a** and the oxide **230b** and a top surface of the insulator **222** may be an acute angle. In that case, the angle formed by the side surfaces of the oxide **230a** and the oxide **230b** and the top surface of the insulator **222** is preferably larger.

(354) There is a curved surface between the side surfaces of the oxide **230a** and the oxide **230b** and a top surface of the oxide **230b**. That is, an end portion of the side surface and an end portion of the top surface are preferably curved (hereinafter also referred to as a round shape). The radius of curvature of the curved surface at end portions of the oxide **230a** and the oxide **230b** is greater than or equal to 3 nm and less than or equal to 10 nm, preferably greater than or equal to 5 nm and less than or equal to 6 nm, for example.

(355) Note that when the end portions are not angular, the coverage with films in later deposition process is improved.

(356) Note that the oxide film is processed by a lithography method. For the processing, a dry etching method or a wet etching method can be employed. A processing employing a dry etching method is suitable for microfabrication.

(357) Note that in the lithography method, first, a resist is exposed to light through a mask. Next, a region exposed to light is removed or left using a developing solution, so that a resist mask is formed. Then, etching treatment is performed through the resist mask, whereby a conductor, a semiconductor, an insulator, or the like can be processed into a desired shape. The resist mask is formed by, for example, exposure of the resist to light using KrF excimer laser light, ArF excimer laser light, or EUV (Extreme Ultraviolet) light. Alternatively, a liquid immersion technique may be employed in which a portion between a substrate and a projection lens is filled with liquid (for example, water) to perform light exposure. An electron beam or an ion beam may be used instead of the above-described light. Note that a mask is not necessary in the case of using an electron beam or an ion beam. To remove the resist mask, dry etching treatment such as ashing or wet etching treatment can be performed, wet etching treatment can be performed after dry etching treatment, or dry etching treatment can be performed after wet etching treatment.

(358) A hard mask formed of an insulator or a conductor may be used instead of the resist mask. In the case where a hard mask is used, a hard mask with a desired shape can be formed by forming an insulating film or a conductive film to be the material of the hard mask over the oxide film **230B**, forming a resist mask thereover, and then etching the material of the hard mask. The etching of the oxide film **230A** and the oxide film **230B** may be performed after the resist mask is removed or with the resist mask left. In the latter case, the resist mask is removed during the etching in some cases. The hard mask may be removed by etching after the etching of the oxide film. In contrast, the hard mask does not need to be removed in the case where the hard mask material does not affect the following process or can be utilized in the following process.

(359) As a dry etching apparatus, a capacitively coupled plasma (CCP) etching apparatus including parallel plate type electrodes can be used. The capacitively coupled plasma etching apparatus including the parallel plate type electrodes may have a structure in which a high-frequency power is applied to one of the parallel plate type electrodes. Alternatively, a structure in which different high-frequency powers are applied to one of the parallel plate type electrodes may be employed. Alternatively, a structure in which high-frequency powers with the same frequency are applied to the parallel plate type electrodes may be employed. Alternatively, a structure in which high-

frequency powers with different frequencies are applied to the parallel plate type electrodes may be employed. Alternatively, a dry etching apparatus including a high-density plasma source can be used. As the dry etching apparatus including a high-density plasma source, an inductively coupled plasma (ICP) etching apparatus can be used, for example.

(360) In some cases, the treatment such as dry etching causes the attachment or diffusion of impurities due to an etching gas or the like to a surface or an inside of the oxide **230a**, the oxide **230b**, or the like. Examples of the impurities include fluorine and chlorine.

(361) In order to remove the impurities or the like, cleaning is performed. Examples of the cleaning method include wet cleaning using a cleaning solution or the like, plasma treatment using plasma, and cleaning by heat treatment, and the cleaning methods may be performed in appropriate combination.

(362) As the wet cleaning, cleaning treatment may be performed using an aqueous solution in which oxalic acid, phosphoric acid, hydrofluoric acid, or the like is diluted with carbonated water or pure water. Alternatively, ultrasonic cleaning using pure water or carbonated water may be performed. In this embodiment, ultrasonic cleaning using pure water or carbonated water is performed.

(363) Next, heat treatment may be performed. As the conditions for the heat treatment, the above-described heat treatment conditions can be used.

(364) Then, an oxide film **230C**, an insulating film **250A**, a conductive film **260A**, a conductive film **260B**, an insulating film **270A**, and an insulating film **271A** are deposited sequentially over the insulator **224**, the oxide **230a**, and the oxide **230b** (see FIG. 13).

(365) The oxide film **230C** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. The oxide film **230C** is deposited by a deposition method similar to that of the oxide film **230A** or the oxide film **230B** in accordance with characteristics required for the oxide **230c**. In this embodiment, the oxide film **230C** is deposited using a target of In:Ga:Zn=1:3:4 [atomic ratio] by a sputtering method.

(366) The insulating film **250A** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(367) Note that oxygen is excited by microwaves to generate high-density oxygen plasma, and the insulating film **250A** is exposed to the oxygen plasma, whereby oxygen can be supplied to the insulating film **250A**, the oxide **230a**, the oxide **230b**, and the oxide film **230C**.

(368) Furthermore, heat treatment may be performed. For the heat treatment, the above-described heat treatment conditions can be used. The heat treatment can reduce the moisture concentration and the hydrogen concentration in the insulating film **250A**.

(369) The conductive film **260A** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. In this embodiment, as the conductive film **260A**, titanium nitride is formed by a sputtering method.

(370) The conductive film **260B** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. When a low-resistance metal film is stacked as the conductive film **260B**, a transistor with a low driving voltage can be provided. In this embodiment, as the conductive film **260B**, tungsten is formed by a sputtering method.

(371) Another conductor may be provided between the insulating film **250A** and the conductive film **260A**. The conductor can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. Here, when an oxide semiconductor that can be used as the oxide **230** is subjected to treatment for reducing resistance, for example, the oxide **30** semiconductor becomes a conductive oxide. Accordingly, an oxide that can be used as the oxide **230** may be deposited and the resistance of the oxide may be reduced in a later step. Note that when an oxide that can be used as the oxide **230** is deposited over the insulating film **250A** in an atmosphere containing oxygen by a sputtering method, oxygen can be added to the insulating film **250A**. When oxygen is added to the insulating film **250A**, the added oxygen can be supplied to the

oxide **230** through the insulating film **250A**.

(372) Subsequently, heat treatment can be performed. For the heat treatment, the above-described heat treatment conditions can be used. Note that the heat treatment is not necessarily performed in some cases. In this embodiment, the treatment is performed in a nitrogen atmosphere at 400° C. for one hour.

(373) The insulating film **270A** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. Since the insulating film **270A** functions as a barrier film, an insulating material having a function of inhibiting passage of oxygen and impurities such as water and hydrogen is used. For example, aluminum oxide, hafnium oxide, or hafnium aluminate is preferably used. Thus, oxidation of the conductor **260** can be prevented. This can also prevent entry of impurities such as water and hydrogen into the oxide **230** through the conductor **260** and the insulator **250**.

(374) The insulating film **271A** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. Here, the thickness of the insulating film **271A** is preferably greater than the thickness of the insulating film **272A** to be formed in a later step. In that case, when the insulator **272** is formed in the later step, the insulator **271** can remain easily over the conductor **260**.

(375) The insulator **271** functions as a hard mask. The provision of the insulator **271** makes it possible for the side surface of the insulator **250**, a side surface of the conductor **260a**, a side surface of the conductor **260b**, a side surface of the conductor **260c**, and the side surface of the insulator **270** to be formed substantially perpendicular to the substrate.

(376) Next, the insulating film **271A** is etched to form the insulator **271**. Then, using the insulator **271** as a mask, the insulating film **250A**, the conductive film **260A**, the conductive film **260B**, and the insulating film **270A** are etched to form the insulator **250**, the conductor **260** (the conductor **260a** and the conductor **260b**), and the insulator **270** (see FIG. 14). Note that after the processing, the following process may be performed without removal of the hard mask. The hard mask can also function as a hard mask used in for adding a dopant, which is to be performed in the following process.

(377) The side surface of the insulator **250**, the side surface of the conductor **260**, and the side surface of the insulator **270** are preferably on the same surface. It is preferable that the surface shared by the side surface of the insulator **250**, the side surface of the conductor **260**, and the side surface of the insulator **270** be substantially perpendicular to the substrate. That is, in a cross-sectional shape, an angle between the top surface of the oxide **230** and the insulator **250**, the conductor **260**, and the insulator **270** is preferably an acute angle and larger. Note that the angle formed by the top surface of the oxide **230**, which is in contact with the insulator **250**, and the side surfaces of the insulator **250**, the conductor **260**, and the insulator **270** may be an acute angle in the cross-sectional shape. In that case, the angle formed by the top surface of the oxide **230**, which is in contact with the insulator **250**, and the side surfaces of the insulator **250**, the conductor **260**, and the insulator **270** is preferably larger.

(378) The insulator **250**, the conductor **260**, and the insulator **270** are formed to at least partly overlap with the conductor **205** and the oxide **230**.

(379) An upper portion of the oxide film **230C** in a region not overlapping with the insulator **250** may be etched by the above etching. In that case, the oxide film **230C** may be thicker in a region overlapping with the insulator **250** than in the region not overlapping with the insulator **250**.

(380) Next, the insulating film **272A** is deposited to cover the oxide film **230C**, the insulator **250**, the conductor **260**, the insulator **270**, and the insulator **271** (see FIG. 15). The insulating film **272A** is preferably deposited by an ALD method, which enables good coverage. By using an ALD method, the insulating film **272A** having a uniform thickness can be formed on the side surfaces of the insulator **250**, the conductor **260**, and the insulator **270** even in a step portion formed by the conductor **260** and the like.

(381) Next, the insulating film 272A is subjected to anisotropic etching treatment, whereby the insulator 272 is formed in contact with the side surfaces of the insulator 250, the conductor 260, and the insulator 270 (see FIG. 16). Dry etching treatment is preferably performed as the anisotropic etching treatment. In this manner, the insulating film deposited on a plane substantially parallel to the surface of the substrate can be removed, so that the insulator 272 can be formed in a self-aligned manner.

(382) The insulator 271 is formed over the insulator 270 here, whereby the insulator 270 can be left even when the insulating film 272A in a portion above the insulator 270 are removed. The height of a structure body composed of the insulator 250, the conductor 260, the insulator 270, and the insulator 271 is made greater than the total height of the oxide 230a, the oxide 230b, and the oxide film 230C, whereby the insulating film 272A on the side surfaces of the oxide 230a and the oxide 230b with the oxide film 230C therebetween can be removed. Furthermore, when the end portions of the oxide 230a and the oxide 230b have a round shape, time taken to remove the insulating film 272A deposited on the side surfaces of the oxide 230a and the oxide 230b with the oxide film 230C therebetween can be shortened, leading to easier formation of the insulator 272.

(383) Next, the oxide film 230C is etched using the insulator 250, the conductor 260, the insulator 270, the insulator 271, and the insulator 272 as masks to remove part of the oxide film 230C, so that the oxide 230c is formed (see FIG. 17). Note that through the present process, the top surface and the side surfaces of the oxide 230b and the side surfaces of the oxide 230a are partly removed in some cases.

(384) Here, the region 231, the region 232, and the region 234 may be formed in the oxide 230a, the oxide 230b, and the oxide 230c. The region 231 and the region 232 are regions whose resistance is reduced by addition of a metal atom such as indium or impurities to metal oxides provided as the oxide 230a, the oxide 230b, and the oxide 230c. Note that each of the regions has higher conductivity than at least the oxide 230b in the region 234.

(385) In order to reduce the resistance of the region 231 and the region 232, a dopant which is at least one of the metal element such as indium and the impurities is added, for example.

(386) Note that as a method for adding the dopant, an ion implantation method by which an ionized source gas is subjected to mass separation and then added, an ion doping method by which an ionized source gas is added without mass separation, a plasma immersion ion implantation method, or the like can be used. In the case of performing mass separation, ion species to be added and its concentration can be controlled properly. On the other hand, in the case of not performing mass separation, ions at a high concentration can be added in a short time. Alternatively, an ion doping method in which atomic or molecular clusters are generated and ionized may be employed. Note that a dopant may also be referred to as an ion, a donor, an acceptor, an impurity, an element, or the like.

(387) Alternatively, a dopant may be added by plasma treatment. In that case, the plasma treatment can be performed with a plasma CVD apparatus, a dry etching apparatus, or an ashing apparatus to add a dopant to the oxide 230a, the oxide 230b, and the oxide 230c.

(388) Furthermore, in the case where an impurity is added as a dopant, a film containing a dopant may be deposited in contact with the region 231. For example, the insulator 274 containing hydrogen, boron, carbon, nitrogen, fluorine, or phosphorus as a dopant is deposited in contact with the region 231 of the oxide 230 (see FIG. 18). Owing to the deposition of the insulator 274 or the heat treatment after the deposition, the resistance of the region 231 is reduced, and the region 232 is formed. It is considered that the dopant in the insulator 274 is diffused into the region 231 and the region 232 and the resistance of the region is reduced.

(389) When the indium content in the oxide 230a, the oxide 230b, and the oxide 230c is increased, the carrier density can be increased and the resistance can be reduced. Accordingly, a metal element that improves the carrier density of the oxide 230a, the oxide 230b, and the oxide 230c, such as indium, can be used as a dopant.

(390) That is, when the content of a metal atom such as indium in the oxide **230a**, the oxide **230b**, and the oxide **230c** is increased in the region **231** and the region **232**, the electron mobility can be increased and the resistance can be reduced.

(391) Accordingly, the atomic ratio of indium to the element M at least in the region **231** is larger than the atomic ratio of indium to the element M in the region **234**.

(392) As the dopant, the element forming an oxygen vacancy, the element trapped by an oxygen vacancy, or the like may be used. Typical examples of the element are hydrogen, boron, carbon, nitrogen, fluorine, phosphorus, sulfur, chlorine, titanium, and a rare gas. Typical examples of the rare gas element are helium, neon, argon, krypton, and xenon.

(393) When the region **232** is provided in the transistor **200**, a high-resistance region is not formed between the region **231** functioning as the source region or the drain region and the region **234** where a channel is formed, so that the on-state current and the mobility of the transistor can be increased. Since the gate does not overlap with the source region and the drain region in the channel length direction owing to the region **232**, formation of unnecessary capacitance can be inhibited. Furthermore, leakage current in a non-conduction state can be reduced by including the region **232**.

(394) Thus, by appropriately selecting the areas of the region **231a** and the region **231b**, a transistor having electrical characteristics necessary for the circuit design can be easily provided.

(395) In this embodiment, the insulator **274** is deposited to cover the insulator **224**, the oxide **230**, the insulator **271**, and the insulator **272** (see FIG. **18**).

(396) For the insulator **274**, silicon nitride, silicon nitride oxide, or silicon oxynitride which is deposited by a CVD method can be used, for example. In this embodiment, silicon nitride oxide is used for the insulator **274**. In the case where the insulator **274** is used as a dielectric of the capacitor **100**, its thickness is greater than or equal to 1 nm and less than or equal to 20 nm, preferably greater than or equal to 3 nm and less than or equal to 10 nm.

(397) When the insulator **274** containing an element serving as an impurity such as nitrogen is deposited in contact with the oxide **230**, impurity elements such as hydrogen and nitrogen, which are contained in a deposition atmosphere of the insulator **274**, are added to the region **231a** and the region **231b**. Oxygen vacancies are formed because of the added impurity elements, and the impurity elements enter the oxygen vacancies mainly in a region of the oxide **230** which is in contact with the insulator **274**, thereby increasing the carrier density and reducing the resistance. At this time, the impurities are diffused also into the region **232** that is not in contact with the insulator **274**, whereby the resistance of the region **232** is reduced.

(398) Therefore, the region **231a** and the region **231b** preferably have a higher concentration of at least one of hydrogen and nitrogen than the region **234**. The concentration of hydrogen or nitrogen is measured by secondary ion mass spectrometry (SIMS) or the like. Here, the concentration of hydrogen or nitrogen in the middle of the region of the oxide **230b** that overlaps with the insulator **250** (for example, a portion of the oxide **230b** which is located nearly equidistant from both side surfaces in the channel length direction of the insulator **250**) is measured as the concentration of hydrogen or nitrogen in the region **234**.

(399) Note that the resistance of the region **231** and the region **232** to which an element that forms an oxygen vacancy or an element trapped by an oxygen vacancy is added is reduced. Typical examples of the element are hydrogen, boron, carbon, nitrogen, fluorine, phosphorus, sulfur, chlorine, titanium, and a rare gas. Typical examples of the rare gas element are helium, neon, argon, krypton, and xenon. Accordingly, the region **231** and the region **232** are made to contain one or more of the above elements.

(400) Alternatively, as the insulator **274**, a film which extracts and absorbs oxygen in the region **231** and the region **232** may be used. When oxygen is extracted, oxygen vacancies are generated in the region **231** and the region **232**. Hydrogen, boron, carbon, nitrogen, fluorine, phosphorus, sulfur, chlorine, titanium, a rare gas, or the like is trapped by oxygen vacancies, whereby the resistance of

the region **231** and the region **232** is reduced.

(401) To deposit the insulator **274** as an insulator containing an element serving as an impurity or an insulator extracting oxygen from the oxide **230**, a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like can be used for the deposition of the insulator **274**.

(402) The insulator **274** containing an element serving as an impurity is preferably deposited in an atmosphere containing at least one of nitrogen and hydrogen. When deposition is performed in such an atmosphere, oxygen vacancies are formed mainly in regions not overlapping with the insulator **250** of the oxide **230b** and the oxide **230c** and the oxygen vacancies and impurity elements such as nitrogen and hydrogen are bonded to each other, leading to an increase in carrier density. In this manner, the region **231a** and the region **231b** with reduced resistance can be formed. For the insulator **274**, for example, silicon nitride, silicon nitride oxide, or silicon oxynitride formed by a CVD method can be used. In this embodiment, silicon nitride oxide is used for the insulator **274**.

(403) The insulator **274** may have a stacked-layer structure of two or more layers of an insulator. The insulator **274** can be formed by a CVD method, an ALD method, a sputtering method, or the like. An ALD method is favorable for deposition on a step portion formed by the oxide **230** or the conductor **260** because of its excellent step coverage, excellent thickness uniformity, and excellent thickness controllability. An insulator with a thickness of greater than or equal to 0.5 nm and less than or equal to 5.0 nm may be formed by an ALD method, and then an insulator with a thickness of greater than or equal to 1 nm and less than or equal to 20 nm, preferably greater than or equal to 3 nm and less than or equal to 10 nm may be stacked thereover by a plasma CVD method, so that the insulator **274** may be formed. For example, over aluminum oxide, hafnium oxide, or an oxide containing aluminum and hafnium (hafnium aluminate) formed by an ALD method, silicon nitride, silicon nitride oxide, silicon oxynitride, or silicon oxide formed by a plasma CVD method is stacked, so that the insulator **274** may be formed. Alternatively, an insulator with a thickness of greater than or equal to 1 nm and less than or equal to 20 nm, preferably greater than or equal to 3 nm and less than or equal to 10 nm may be formed to be a single-layer insulator **274** by a plasma CVD method. For example, silicon nitride, silicon nitride oxide, silicon oxynitride, or silicon oxide formed by a plasma CVD method may be the insulator **274**.

(404) Accordingly, the source region and the drain region can be formed in a self-aligned manner owing to the deposition of the insulator **274**. Thus, minute or highly integrated semiconductor devices can also be manufactured with high yield.

(405) Here, the top surfaces and the side surfaces of the conductor **260** and the insulator **250** are covered with the insulator **270** and the insulator **272**, whereby impurity elements such as nitrogen and hydrogen can be prevented from entering the conductor **260** and the insulator **250**. Thus, the impurity elements such as nitrogen and hydrogen can be prevented from entering the region **234** functioning as the channel formation region of the transistor **200** through the conductor **260** and the insulator **250**. Accordingly, the transistor **200** having favorable electrical characteristics can be provided.

(406) Note that although the region **231**, the region **232**, and the region **234** are formed by the reduction in the resistance of the oxide **230** owing to the deposition of the insulator **274** in the above, this embodiment is not limited thereto. For example, each region and the like may be formed by dopant addition treatment or plasma treatment, or the combination of these treatments.

(407) For example, plasma treatment may be performed on the oxide **230** using the insulator **250**, the conductor **260**, the insulator **272**, the insulator **270**, and the insulator **271** as masks. The plasma treatment is performed in, for example, an atmosphere containing the above-described element forming an oxygen vacancy or the above-described element trapped by an oxygen vacancy. For example, the plasma treatment is performed using an argon gas and a nitrogen gas.

(408) Subsequently, heat treatment can be performed. For the heat treatment, the above-described

heat treatment conditions can be used. The heat treatment allows diffusion of the added dopant into the region **232** of the oxide **230**, resulting in an increase in on-state current.

(409) Next, a conductive film **130A** is formed to cover the insulator **274** (see FIG. **19**). The conductive film **130A** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(410) Then, the conductive film **130A** is processed by a lithography method to form the conductor **130** (see FIG. **20**). For processing the conductive film **130A**, a dry etching method, a wet etching method, or a combination of these methods can be used. A dry etching method in which anisotropic etching can be achieved is preferable because of its excellent microfabrication. In contrast, by using wet etching, which allows isotropic etching, the conductive film **130A** on the side surfaces of the oxide **230**, the side surfaces of the insulator **250**, and side surfaces of the insulator **272** is easily removed. Thus, processing in which the dry etching method and the wet etching method are combined is preferable because the conductor **130** with favorable shape can be formed.

(411) In this embodiment, as illustrated in FIG. **20(B)** and FIG. **20(D)**, part of the conductor **130** provided over the oxide **230** is provided to extend outward from the oxide **230**. Specifically, the conductor **130** is provided to extend beyond the oxide **230** to the B side in FIG. **20(B)**, and the conductor **130** is provided to extend beyond the oxide **230** to the E side and the F side in FIG. **20(D)**.

(412) Such a shape is preferable because the capacitor **100** can form capacitance not only between the top surface of the oxide **230** and the conductor **130** but also between the side surface of the oxide **230** and the conductor **130**. In contrast, when there is a limitation on the area occupied by the cell **600**, the conductor **130** is formed so as to extend beyond the oxide **230** as little as possible; thus, the cell **600** can be miniaturized, so that the semiconductor device can be highly integrated.

(413) Then, the insulator **280** is deposited over the insulator **274** and the conductor **130** (see FIG. **21**). The insulator **280** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. Alternatively, the insulator **280** can be deposited by a spin coating method, a dipping method, a droplet discharging method (such as an ink-jet method), a printing method (such as screen printing or offset printing), a doctor knife method, a roll coater method, a curtain coater method, or the like. In this embodiment, silicon oxynitride is used for the insulating film.

(414) Note that the insulator **280** is preferably formed such that its top surface has planarity. For example, the insulator **280** may have a flat top surface right after the deposition of the insulating film to be the insulator **280**. Alternatively, for example, the insulator **280** may have a flat top surface by removing the insulator from the top surface after the deposition so that the top surface becomes parallel to a reference surface such as a rear surface of the substrate. Such treatment is referred to as planarization treatment. Examples of the planarization treatment include CMP treatment and dry etching treatment. In this embodiment, CMP treatment is used as the planarization treatment. Note that the top surface of the insulator **280** does not necessarily have planarity.

(415) Then, an opening reaching the region **231** of the oxide **230**, an opening reaching the conductor **130**, an opening reaching the conductor **260**, and an opening reaching the conductor **205** are formed in the insulator **280** and the insulator **274**, in the insulator **280**, in the insulator **280**, the insulator **274**, the insulator **271**, and the insulator **270**, and in the insulator **280**, the insulator **274**, the insulator **224**, the insulator **222**, and the insulator **220**, respectively. The openings are formed by a lithography method.

(416) Note that in order that the conductor **252a** may be provided in contact with the side surface of the oxide **230**, the opening reaching the oxide **230** is formed such that the side surface of the oxide **230** is exposed in the opening.

(417) Next, the conductor **252** (the conductor **252a**, the conductor **252b**, the conductor **252c**, and the conductor **252d**) is formed (see FIG. **22**). Furthermore, the conductor **256** electrically connected

to the conductor **252** may be formed as needed (see FIG. **22**).

(418) Through the above process, the semiconductor device including the transistor **200** and the capacitor **100** can be manufactured. As illustrated in FIG. **5** to FIG. **22**, by using the method for manufacturing a semiconductor device described in this embodiment, the transistor **200** and the capacitor **100** can be manufactured.

(419) According to one embodiment of the present invention, a semiconductor device that can be miniaturized or highly integrated can be provided. Alternatively, according to one embodiment of the present invention, a semiconductor device with favorable electrical characteristics can be provided. Alternatively, according to one embodiment of the present invention, a semiconductor device with a low off-state current can be provided. Alternatively, according to one embodiment of the present invention, a transistor with a high on-state current can be provided. Alternatively, according to one embodiment of the present invention, a highly reliable semiconductor device can be provided. Alternatively, according to one embodiment of the present invention, a semiconductor device with low power consumption can be provided. Alternatively, according to one embodiment of the present invention, a semiconductor device with high productivity can be provided.

(420) The structures, methods, and the like in this embodiment described above can be combined as appropriate with the structures, methods, and the like described in the other embodiments.

Embodiment 2

(421) An example of a semiconductor device including a transistor **202** of one embodiment of the present invention will be described below.

(422) In the semiconductor device of this embodiment, materials similar to those in Embodiment 1 can be used for components with the same reference numerals as the semiconductor device in Embodiment 1. Unless otherwise specified, the components formed in this embodiment can obtain structural characteristics and effects similar to those of the components described in Embodiment 1, and description thereof is omitted.

(423) <Structure Example 3 of Semiconductor Device>

(424) FIG. **23(A)**, FIG. **23(B)**, FIG. **23(C)**, and FIG. **23(D)** are a top view and cross-sectional views of the transistor **202** of one embodiment of the present invention.

(425) FIG. **23(A)** is a top view of the transistor **202**. FIG. **23(B)**, FIG. **23(C)**, and FIG. **23(D)** are cross-sectional views of the transistor **202**. Here, FIG. **23(B)** is a cross-sectional view of a portion denoted by dashed-dotted line A-B in FIG. **23(A)**, and is also a cross-sectional view of the transistor **202** in the channel length direction. FIG. **23(C)** is a cross-sectional view of a portion denoted by dashed-dotted line C-D in FIG. **23(A)**, and is also a cross-sectional view of the transistor **202** in the channel width direction. FIG. **23(D)** is a cross-sectional view of a portion denoted by dashed-dotted line E-F in FIG. **23(A)**. For simplification of the drawing, some components are omitted in the top view in FIG. **23(A)**.

(426) [Transistor **202**]

(427) As illustrated in FIG. **23**, the transistor **202** includes the insulator **208** placed over the substrate (not illustrated); the conductor **209** over the insulator **210** placed over the insulator **208**; the insulator **212** placed to be embedded between the conductors **209**; the insulator **216** placed over the conductor **209** and the insulator **212**; the conductor **203** and the conductor **205** that are placed to be embedded in the insulator **216**; the insulator **220** placed over the insulator **216**, the conductor **203**, and the conductor **205**; the insulator **222** placed over the insulator **220**; the insulator **224** placed over the insulator **222**; the oxide **230** (the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d**) placed over the insulator **224**; the insulator **250** (an insulator **250a** and an insulator **250b**) placed over the oxide **230**; the conductor **260** (the conductor **260a** and the conductor **260b**) placed over the insulator **250**; the insulator **270** placed over the conductor **260**; the insulator **271** placed over the insulator **270**; the insulator **272** placed in contact with at least the side surface of the insulator **250** and the side surface of the conductor **260**; an insulator **273** placed in contact with part of the top surface and part of the side surface of the insulator **272**; and the insulator **274** placed

to cover at least the oxide **230**, the insulator **271**, the insulator **272**, and the insulator **273**.

(428) The insulator **280** is placed to cover the transistor **202**.

(429) Note that the insulator **212** can be formed by polishing of an insulating film placed to cover the conductor **209** by a CMP method or the like to expose the conductor **209**. Thus, surfaces of the insulator **212** and the conductor **209** have high planarity.

(430) The conductor **203** and the conductor **205** are formed to be embedded in the opening portions provided in the insulator **216**. The conductors can be formed by polishing a conductive film placed to cover the insulator **216** and the opening portions by a CMP method or the like to expose the insulator **216**. Thus, surfaces of the insulator **216**, the conductor **203**, and the conductor **205** have high planarity.

(431) The insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a** have an opening. The oxide **230b** and the oxide **230c** are electrically connected to the conductor **203** through the opening. When the oxide **230b** and the oxide **230c** are connected to the conductor **203** without through the oxide **230a**, the series resistance and the contact resistance can be reduced. With such a structure, a semiconductor device with favorable electrical characteristics can be obtained. Specifically, a transistor with an increased on-state current and a semiconductor device including the transistor are obtained.

(432) The conductor **209** may have a stacked-layer structure. In that case, a conductor having a better oxidation resistance than a conductor in a lower layer is preferably placed over a conductor having better conductivity than a conductor in an upper layer. When a material that is hardly oxidized is used for the upper layer in the conductor **209**, oxidation of the conductor **209** can be inhibited at the time of forming the insulator **216**, at the time of forming the opening portion to be provided in the insulator **216**, and at the time of forming the conductor **205**. Thus, an increase in the electrical resistance due to oxidation of the conductor **209** can be inhibited. That is, the contact between the conductor **209** and the conductor **205** becomes favorable.

(433) Note that although the transistor **202** has, as illustrated in FIG. **23**, a structure in which the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d** are stacked, the present invention is not limited thereto. For example, a two-layer structure of the oxide **230a** and the oxide **230c**, a two-layer structure of the oxide **230b** and the oxide **230c**, a three-layer structure of the oxide **230a**, the oxide **230c**, and the oxide **230d**, or a three-layer structure of the oxide **230b**, the oxide **230c**, and the oxide **230d** may be employed. That is, one of the oxide **230a** and the oxide **230b** is not necessarily provided. Alternatively, the oxide **230d** is not necessarily provided. Alternatively, a stacked-layer structure of five or more layers may be employed. Alternatively, a single layer of only the oxide **230c** or only the oxide **230c** and the oxide **230d** may be provided. Although the transistor **202** has a structure in which the conductor **260a** and the conductor **260b** are stacked, the present invention is not limited thereto. For example, a single layer or a stacked-layer structure of three or more layers may be employed.

(434) Here, an enlarged view of the region **239** in the vicinity of a channel, which is surrounded by a dashed line in FIG. **23(B)**, is illustrated in FIG. **24**.

(435) As illustrated in FIG. **23(B)** and FIG. **24**, the oxide **230** includes the region **232** (the region **232a** and the region **232b**) between the region **234** functioning as a channel formation region of the transistor **202** and the region **231** (the region **231a** and the region **231b**) functioning as a source region or a drain region. The region **231** functioning as the source region or the drain region is a region having a high carrier density and reduced resistance. In addition, the region **234** functioning as the channel formation region is a region having a lower carrier density than the region **231** functioning as the source region or the drain region. Moreover, the region **232** is a region having a lower carrier density than the region **231** functioning as the source region or the drain region and having a higher carrier density than the region **234** functioning as the channel formation region.

(436) In the region **231**, a region **233** connected to the conductor **252a** preferably has a higher carrier density and a lower resistance than the region **231**. The region **233** is provided in the region

231, so that contact resistance between the oxide **230** and the conductor **252a** can be reduced and the transistor **202** can have favorable electrical characteristics. The region **233** can be referred to as a contact region.

(437) The region **231**, the region **232**, and the region **233** can be provided by addition of a rare gas typified by helium or argon to the oxide **230**. For the addition of the rare gas, for example, an ion implantation method by which an ionized source gas is subjected to mass separation and then added, an ion doping method by which an ionized source gas is added without mass separation, a plasma immersion ion implantation method, or plasma treatment can be used.

(438) It can be considered that when the rare gas is added to the oxide **230**, a bond between a metal element and an oxygen atom in the oxide **230** is broken, and oxygen vacancies are generated in the oxide **230**. When impurities such as hydrogen are trapped by the oxygen vacancies, carriers are generated, and the resistance of the oxide **230**, that is, the resistance of the region **231**, the region **232**, and the region **233** is reduced. Impurities such as hydrogen exist in the oxide **230** in some cases. In that case, the impurities may exist without being connected to a metal element or an oxygen atom. The impurities can be supplied from an insulator provided in contact with the oxide **230**, for example, from the insulator **274**.

(439) The region **234** is a highly purified region where oxygen vacancies and impurities such as hydrogen are reduced as much as possible. The highly purified oxide becomes a substantially intrinsic region, and the region **234** can function as a channel formation region.

(440) Although FIG. **23** and FIG. **24** illustrate a state where the region **232** overlaps with the conductor **260** functioning as a gate electrode, this embodiment is not limited thereto. Depending on the formation method of the region **231** and the region **232**, the region **232** does not overlap with the conductor **260** functioning as a gate electrode in some cases.

(441) The region **232** can be a region having a lower carrier density than the region **231** functioning as the source region or the drain region and having a higher carrier density than the region **234** functioning as the channel formation region. In that case, the region **232** functions as a junction region between the channel formation region and the source region or the drain region.

(442) The provision of the junction region is preferable because a high-resistance region is not formed between the region **231** functioning as the source region or the drain region and the region **234** functioning as the channel formation region, thereby increasing on-state current of the transistor.

(443) The region **234** overlaps with the conductor **260**. The region **234** is placed between the region **232a** and the region **232b**, and the concentration of at least one of a metal element such as indium and an impurity element such as hydrogen or nitrogen in the region **234** is preferably lower than that in each of the region **231** and the region **232**.

(444) In addition, in the oxide **230**, boundaries between the region **231**, the region **232**, the region **233**, and the region **234** cannot be observed clearly in some cases. The concentrations of a metal element such as indium and an impurity element such as hydrogen or nitrogen, which are detected in each region, may be not only gradually changed between the regions but also continuously changed in each region (also referred to as gradation). That is, the region closer to the region **234**, from the region **231** to the region **232**, preferably has a lower concentration of a metal element such as indium and an impurity element such as hydrogen or nitrogen.

(445) Furthermore, in FIG. **23(B)** and FIG. **24**, the region **234**, the region **231**, the region **232**, and the region **233** are formed in the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d**; however, the present invention is not limited thereto, and these regions are formed at least in the oxide **230c**. Alternatively, these regions may be formed only in the oxide **230c** and the oxide **230d**, for example. Although the boundaries between the regions are indicated substantially perpendicularly to the interface between the insulator **224** and the oxide **230** in the drawings, this embodiment is not limited thereto. For example, the region **232** may project to the region **234** side in the vicinity of the surface of the oxide **230c**, and recede to the region **231** side in the vicinity of a

bottom surface of the oxide **230c**.

(446) When the insulator **250** has a stacked-layer structure including the insulator **250a** and the insulator **250b**, and the insulator **250b** is formed over the insulator **250a** in an atmosphere containing oxygen, for example, a larger amount of oxygen, that is, excess oxygen can be contained in **250a**.

(447) The insulator **272** is preferably provided in contact with the side surface of the insulator **250**.

(448) Furthermore, the transistor **202** is preferably surrounded by an insulator which has a barrier property and prevents entry of impurities such as water and hydrogen.

(449) The structure of a semiconductor device including the transistor **202** of one embodiment of the present invention will be described in detail below.

(450) In the transistor **202**, the conductor **260** functions as the first gate electrode in some cases. Furthermore, the conductor **205** functions as a second gate electrode in some cases. In that case, by changing a potential applied to the conductor **205** not in synchronization with but independently of a potential applied to the conductor **260**, the threshold voltage of the transistor **202** can be controlled. In particular, by applying a negative potential to the conductor **205**, the threshold voltage of the transistor **202** can be substantially shifted positively. In addition, when the threshold voltage of the transistor **202** is higher than 0 V, the off-state current can be reduced. Accordingly, a drain current when a voltage applied to the conductor **260** is 0 V can be reduced.

(451) The conductor **205** functioning as a second gate electrode is placed to overlap with the oxide **230** and the conductor **260**.

(452) That is, the channel formation region in the region **234** can be electrically surrounded by the electric field of the conductor **260** functioning as the first gate electrode and the electric field of the conductor **205** functioning as the second gate electrode. In this specification, a transistor structure in which the channel formation region is electrically surrounded by the electric fields of the first gate electrode and the second gate electrode is referred to as a surrounded channel (S-channel) structure.

(453) In the conductor **205**, the conductor **205a** is formed in contact with an inner wall of the opening in an insulator **214** and the insulator **216** and the conductor **205b** is formed on the inner side. Here, top surfaces of the conductor **205a** and the conductor **205b** can be substantially level with the top surface of the insulator **216**. Note that although the transistor **202** has a structure in which the conductor **205a** and the conductor **205b** are stacked, the present invention is not limited thereto. For example, only the conductor **205b** may be provided.

(454) Here, for the conductor **205a**, a conductive material having a function of inhibiting diffusion of impurities such as a hydrogen atom, a hydrogen molecule, a water molecule, a nitrogen atom, a nitrogen molecule, a nitrogen oxide molecule (N.sub.2O, NO, NO.sub.2, and the like), and a copper atom (a conductive material through which the above impurities are less likely to pass) is preferably used. Moreover, it is preferable to use a conductive material having a function of inhibiting diffusion of oxygen (for example, at least one of oxygen atoms and oxygen molecules), that is, a conductive material through which the above oxygen is less likely to pass. Note that in this specification, a function of inhibiting diffusion of impurities or oxygen means a function of inhibiting diffusion of any one or all of the above impurities and the above oxygen.

(455) When the conductor **205a** has a function of inhibiting diffusion of oxygen, the conductivity of the conductor **205b** can be prevented from being reduced because of oxidation. As a conductive material having a function of inhibiting diffusion of oxygen, for example, tantalum, tantalum nitride, ruthenium, or ruthenium oxide is preferably used. Accordingly, the conductor **205a** may be a single layer or stacked layers of the above conductive materials. Thus, impurities such as hydrogen and water can be prevented from being diffused to the transistor **202** side through the conductor **205** from the substrate side from the insulator **214**.

(456) Furthermore, for the conductor **205b**, a conductive material containing tungsten, copper, or aluminum as its main component is preferably used. Note that the conductor **205b** is a single layer

in the drawing but may have a stacked-layer structure, and for example, stacked layers of titanium, titanium nitride, and any of the above conductive materials may be used.

(457) The conductor **209** can function as an electrode or a wiring. When the conductor **205** is used as the second gate electrode of the transistor **202**, part of the conductor **209** can function as a gate wiring. In that case, the conductor **205** and the conductor **252d** may be electrically connected to each other through the conductor **207** including the conductor **207a** and the conductor **207b** formed over the conductor **207a**, and the conductor **209**. The conductor **207** can be formed in the same step as the conductor **203** and the conductor **205**.

(458) The conductor **209** is electrically connected to the oxide **230** through the conductor **203**, and can function as a source wiring or a drain wiring of the transistor **202**. The conductor **209** may be used as an electrode for electrical connection with the element or the wiring positioned below the insulator **210**.

(459) The conductor **203** and the conductor **209** are provided under the oxide **230** to overlap with each other, so that a plug or an electrode for connecting the transistor **202** and the element or the wiring positioned below the insulator **210** can be provided to overlap with the transistor **202**. Thus, the cell size can be reduced, which is preferable.

(460) A material similar to that for the insulator **210** described in Embodiment 1 can be used for the insulator **210**.

(461) Moreover, the insulator **212** and the insulator **216** functioning as interlayer films preferably have a lower permittivity than the insulator **210**. In the case where a material with a low permittivity is used for an interlayer film, the parasitic capacitance generated between wirings can be reduced. A material similar to that for the insulator **208**, the insulator **216**, and the insulator **280** described in Embodiment 1 can be used for the insulator **212** and the insulator **216** functioning as interlayer films.

(462) The insulator **220**, the insulator **222**, and the insulator **224** each function as a gate insulator. A material similar to that for the insulator **220**, the insulator **222**, and the insulator **224** described in Embodiment 1 can be used for the insulator **220**, the insulator **222**, and the insulator **224**.

(463) The oxide **230** includes the oxide **230a**, the oxide **230b** over the oxide **230a**, the oxide **230c** over the oxide **230b**, and the oxide **230d** over the oxide **230c**. The oxide **230** also includes the region **231**, the region **232**, the region **233**, and the region **234**. Note that at least part of the region **231** is preferably in contact with the insulator **274**. Moreover, it is preferable that the concentration of at least one of hydrogen, nitrogen, and a metal element such as indium in at least part of the region **231** be higher than that in the region **234**.

(464) When the transistor **202** is turned on, the region **231a** or the region **231b** functions as the source region or the drain region. In addition, at least part of the region **234** functions as a region where a channel is formed.

(465) Here, as illustrated in FIG. **24**, the oxide **230** preferably includes the region **232**. When the region **232** is a junction region, on-state current can be increased and leakage current (off-state current) in a non-conduction state can be reduced.

(466) When the oxide **230c** is provided over the oxide **230a** and the oxide **230b**, impurities can be inhibited from being diffused into the oxide **230b** from the components formed below the oxide **230a**. Moreover, when the oxide **230c** is below the oxide **230d**, impurities can be inhibited from being diffused into the oxide **230c** from the components formed above the oxide **230d**.

(467) That is, the region **234** provided in the oxide **230c** is surrounded by the oxide **230a**, the oxide **230b**, and the oxide **230d**, the concentration of impurities such as hydrogen and nitrogen in the region can be kept low, and the oxygen concentration can be kept high. A semiconductor device using the oxide **230** having such a structure has favorable electrical characteristics and high reliability.

(468) The oxide **230** has a curved surface between the side surface and the top surface. That is, an end portion of the side surface and an end portion of the top surface are preferably curved

(hereinafter also referred to as a round shape). The radius of curvature of the curved surface at an end portion of the oxide **230c** is greater than or equal to 3 nm and less than or equal to 10 nm, preferably greater than or equal to 5 nm and less than or equal to 6 nm, for example.

(469) A material similar to that for the oxide **230** described in Embodiment 1 can be used for the oxide **230**.

(470) Here, the region **234** of the oxide **230** will be described.

(471) The region **234** preferably has a stacked-layer structure of oxides which differ in the atomic ratio of metal elements. Specifically, in the case of the stacked-layer structure of the oxide **230a**, the oxide **230b**, and the oxide **230c**, the atomic ratio of the element M to constituent elements in the metal oxide used as the oxide **230a** is preferably greater than the atomic ratio of the element M to constituent elements in the metal oxide used as the oxide **230b**. Moreover, the atomic ratio of the element M to constituent elements in the metal oxide used as the oxide **230b** is preferably greater than the atomic ratio of the element M to constituent elements in the metal oxide used as the oxide **230c**. Furthermore, the atomic ratio of the element M to In in the metal oxide used as the oxide **230a** is preferably greater than the atomic ratio of the element M to In in the metal oxide used as the oxide **230b**. Furthermore, the atomic ratio of the element M to In in the metal oxide used as the oxide **230b** is preferably greater than the atomic ratio of the element M to In in the metal oxide used as the oxide **230c**. Moreover, the atomic ratio of In to the element M in the metal oxide used as the oxide **230b** is preferably greater than the atomic ratio of In to the element M in the metal oxide used as the oxide **230a**. Furthermore, the atomic ratio of In to the element M in the metal oxide used as the oxide **230c** is preferably greater than the atomic ratio of In to the element M in the metal oxide used as the oxide **230b**. As the oxide **230d**, a metal oxide which can be used as the oxide **230a**, the oxide **230b**, or the oxide **230c** can be used.

(472) As the oxide **230a** and the oxide **230b**, for example, a metal oxide having a composition of In:Ga:Zn=1:3:4, In:Ga:Zn=1:3:2, or In:Ga:Zn=1:1:1 can be used. As the oxide **230c**, for example, a metal oxide having a composition of In:Ga:Zn=4:2:3, In:Ga:Zn=1:1:1, or In:Ga:Zn=5:1:6 can be used. As the oxide **230d**, for example, a metal oxide having a composition of In:Ga:Zn=1:3:4, In:Ga:Zn=1:3:2, In:Ga:Zn=4:2:3, or In:Ga:Zn=1:1:1 can be used. Note that the above composition represents the atomic ratio of an oxide formed over a substrate or the atomic ratio of a sputtering target.

(473) A combination of a metal oxide having a composition of In:Ga:Zn=1:3:4 as the oxide **230a**, a metal oxide having a composition of In:Ga:Zn=1:1:1 as the oxide **230b**, a metal oxide having a composition of In:Ga:Zn=4:2:3 as the oxide **230c**, and a metal oxide having a composition of In:Ga:Zn=1:1:1 as the oxide **230d** is particularly preferable because the oxide **230c** can be interposed between the oxide **230a**, the oxide **230b**, and the oxide **230d** each having a wider energy gap. Here, each of the oxide **230a**, the oxide **230b**, and the oxide **230d** having a wide energy gap is referred to as a wide gap, and the oxide **230c** having a relatively narrow energy gap is referred to as a narrow gap in some cases.

(474) Next, the region **231** of the oxide **230** is described.

(475) The region **231** is a region whose resistance is reduced by addition of a metal atom such as indium, a rare gas such as helium or argon, or impurities such as hydrogen and nitrogen to a metal oxide provided as the oxide **230**. Note that each region **231** has higher conductivity than at least the oxide **230c** in the region **234**. Note that for addition of a metal atom, a rare gas, or impurities to the region **231**, for example, a dopant which is at least one of a metal element, a rare gas, and impurities is added by plasma treatment, an ion implantation method by which an ionized source gas is subjected to mass separation and then added, an ion doping method by which an ionized source gas is added without mass separation, a plasma immersion ion implantation method, or plasma treatment.

(476) That is, when the content of a metal atom such as indium in the region **231** of the oxide **230** is increased, the electron mobility can be increased and the resistance can be reduced.

(477) Furthermore, when the insulator **274** containing impurity elements is deposited in contact with the oxide **230**, impurities can be added to the region **231**.

(478) That is, the resistance of the region **231** to which an element that forms an oxygen vacancy or an element trapped by an oxygen vacancy is added is reduced. Typical examples of the element are hydrogen, boron, carbon, nitrogen, fluorine, phosphorus, sulfur, chlorine, titanium, and a rare gas. Typical examples of the rare gas element are helium, neon, argon, krypton, and xenon.

Accordingly, the region **231** is made to contain one or more of the above elements.

(479) Alternatively, as the insulator **274**, a film which extracts and absorbs oxygen in the region **231** may be used. When oxygen is extracted, oxygen vacancies are generated in the region **231**.

Hydrogen, boron, carbon, nitrogen, fluorine, phosphorus, sulfur, chlorine, titanium, a rare gas, or the like is trapped by oxygen vacancies, whereby the resistance of the region **231** is reduced.

(480) The width of the region **232** in the channel length direction can be controlled by the widths of the insulator **272** and the insulator **273**.

(481) Thus, by appropriately selecting the area of the region **232**, a transistor having electrical characteristics necessary for the circuit design can be easily provided.

(482) The insulator **250** functions as a gate insulating film. The insulator **250** is preferably placed in contact with a top surface of the oxide **230d**. The insulator **250** is preferably formed using an insulator from which oxygen is released by heating. The insulator **250** is an oxide film of which the amount of released oxygen converted into oxygen atoms is greater than or equal to 1.0×10^{18} atoms/cm², preferably greater than or equal to 3.0×10^{20} atoms/cm² in thermal desorption spectroscopy analysis (TDS analysis), for example. Note that the temperature of the film surface in the TDS analysis is preferably in a range higher than or equal to 100° C. and lower than or equal to 700° C., or higher than or equal to 100° C. and lower than or equal to 500° C.

(483) For example, the insulator **250** may have a stacked-layer structure including the insulator **250a** and the insulator **250b**. When an insulator from which oxygen is released by heating is provided as the insulator **250a** in contact with the top surface of the oxide **230d**, oxygen can be effectively supplied to the region **234** of the oxide **230c**. Furthermore, as in the insulator **224**, the concentration of impurities such as water and hydrogen in the insulator **250a** is preferably reduced. The thickness of the insulator **250a** is greater than or equal to 1 nm and less than or equal to 20 nm, preferably greater than or equal to 5 nm and less than or equal to 10 nm.

(484) The insulator **250b** is preferably an insulator that can supply oxygen to the insulator **250a** at or after the formation of the insulator **250b**. Such an insulator can be formed in an atmosphere containing oxygen or using a target containing oxygen. For example, aluminum oxide is formed in an atmosphere containing oxygen by a sputtering method. The thickness of the insulator **250b** is greater than or equal to 1 nm and less than or equal to 20 nm, preferably greater than or equal to 5 nm and less than or equal to 10 nm.

(485) The insulator **250b** is provided over the insulator **250a**, whereby a larger amount of oxygen, that is, excess oxygen can be contained in the insulator **250a**.

(486) The conductor **260** functioning as the first gate electrode includes the conductor **260a** and the conductor **260b** over the conductor **260a**. Titanium nitride or the like is preferably used for the conductor **260a**. Moreover, a metal with high conductivity such as tungsten can be used for the conductor **260b**, for example.

(487) In the case where potentials are applied to the conductor **260** and the conductor **205**, the channel formation region formed in the oxide **230** can be covered with an electric field generated from the conductor **260** and an electric field generated from the conductor **205**.

(488) That is, the channel formation region in the region **234** can be electrically surrounded by the electric field of the conductor **260** functioning as the first gate electrode and the electric field of the conductor **205** functioning as the second gate electrode.

(489) The insulator **272** functioning as a barrier film is provided in contact with the side surface of the insulator **250** and the side surface of the conductor **260**. The insulator **270** functioning as a

barrier film is provided over the conductor **260**.

(490) Here, a material similar to that for the insulator **270** described in Embodiment 1 and a material similar to that for the insulator **272** described in Embodiment 1 can be used for the insulator **270** and the insulator **272**, respectively.

(491) In the case where the transistor is miniaturized and formed so that a channel length is approximately greater than or equal to 10 nm and less than or equal to 30 nm, impurity elements in the structure bodies provided in the vicinity of the transistor **202** might be diffused, and the region **231a** and the region **231b**, or the region **232a** and the region **232b** might be electrically connected to each other.

(492) In view of the above, the insulator **272** and the insulator **273** are formed as described in this embodiment so that impurities such as hydrogen and water can be inhibited from entering the insulator **250** and the conductor **260**, and oxygen in the insulator **250** can be prevented from being diffused to the outside. Accordingly, when a first gate voltage is 0 V, the source region and the drain region can be prevented from being electrically connected to each other directly or through the region **232** or the like.

(493) The insulator **273** preferably has a lower permittivity than the insulator **272**. When a material with a low permittivity is used for an interlayer film, the parasitic capacitance generated between the conductor **130** and the conductor **260**, which is described later, can be reduced. A material similar to that for the insulator **212** and the insulator **216** can be used for the insulator **273**.

(494) The insulator **274** is provided to cover at least the oxide **230**, the insulator **271**, the insulator **272**, and the insulator **273**.

(495) Moreover, for the insulator **274**, an insulating material having a function of inhibiting passage of oxygen and impurities such as water and hydrogen is preferably used. For example, for the insulator **274**, silicon nitride, silicon nitride oxide, silicon oxynitride, aluminum nitride, or aluminum nitride oxide is preferably used. When such an insulator **274** is formed, entry of oxygen through the insulator **274** and supply of oxygen to oxygen vacancies in the region **231a** and the region **231b**, which decrease the carrier density, can be prevented. Furthermore, impurities such as water and hydrogen can be prevented from passing through the insulator **274** and being diffused into the region **234**.

(496) Note that when the region **231** is provided by deposition of the insulator **274**, the insulator **274** preferably contains at least one of hydrogen and nitrogen. When an insulator including impurities such as hydrogen and nitrogen is used as the insulator **274**, impurities such as hydrogen and nitrogen are added to the oxide **230**, so that the resistance of the region **231** can be reduced in the oxide **230**.

(497) The insulator **280** functioning as an interlayer film is preferably provided over the insulator **274**. As in the insulator **224** or the like, the concentration of impurities such as water and hydrogen in the insulator **280** is preferably reduced. Note that the insulator **280** may have a stacked-layer structure of similar insulators.

(498) [Capacitor **101**]

(499) As illustrated in FIG. **23**, the capacitor **101** shares some components with the transistor **202**. This embodiment shows an example in which part of the region **231b** provided in the oxide **230** of the transistor **202** functions as one electrode of the capacitor **101**.

(500) The capacitor **101** includes part of the region **231b** of the oxide **230**, the insulator **274**, and the conductors **130** (a conductor **130a** and a conductor **130b**) over the insulator **274**. Furthermore, at least part of the conductor **130** is preferably placed to overlap with part of the region **231b**.

(501) The part of the region **231b** of the oxide **230** functions as one electrode of the capacitor **101** and the conductor **130** functions as the other electrode of the capacitor **101**. That is, the region **231b** functions as both one of the source and the drain of the transistor **202** and one electrode of the capacitor **101**. Part of the insulator **274** functions as a dielectric of the capacitor **101**.

(502) Here, the side surface of the conductor **260** functioning as a first gate electrode of the

transistor **202** is provided with the insulator **272** and the insulator **273**. Since the insulator **272** and the insulator **273** are provided between the conductor **260** and the conductor **130**, the parasitic capacitance between the conductor **260** and the conductor **130** can be reduced.

(503) The conductor **130** preferably has a stacked-layer structure including the conductor **130a** and the conductor **130b** placed over the conductor **130a**. For example, a conductive material containing titanium, titanium nitride, tantalum, or tantalum nitride as its main component is preferably used for the conductor **130a**, and a conductive material containing tungsten, copper, or aluminum as its main component is preferably used for the conductor **130b**. The conductor **130** may have a single-layer structure or a stacked-layer structure of three or more layers.

(504) [Cell **601**]

(505) The semiconductor device of one embodiment of the present invention includes the transistor **202**, the capacitor **101**, and the insulator **280** functioning as an interlayer film.

(506) Furthermore, the conductor **252** (the conductor **252a**, the conductor **252b**, the conductor **252c**, and the conductor **252d**) functioning as a plug that is electrically connected to the transistor **202** and the capacitor **101** is included.

(507) As a plug electrically connected to the conductor **130** functioning as the electrode of the capacitor **101**, the conductor **252b** may be provided. The conductor **130** can function as the electrodes of the capacitors **101** of a plurality of cells **601**. Thus, the conductor **252b** is not necessarily provided in each cell **601** and the number of plugs to be provided in the plurality of cells may be smaller than the number of cells. For example, in a cell array in which the cells **601** are arranged in a matrix, one plug may be provided for each row or one plug may be provided for each column.

(508) The conductor **252** is formed in contact with an inner wall of an opening in the insulator **280**. Here, the top surface of the conductor **252** can be substantially level with the top surface of the insulator **280**. Note that although the conductor **252** in FIG. **23** has a two-layer structure, the present invention is not limited thereto. For example, the conductor **252** may be a single layer or have a stacked-layer structure of three or more layers.

(509) The insulator **280** is preferably provided to cover the insulator **274** and the conductor **130**. As in the insulator **224** or the like, the concentration of impurities such as water and hydrogen in the insulator **280** is preferably reduced. Note that the insulator **280** may have a stacked-layer structure of similar insulators.

(510) The insulator **280** preferably has a lower permittivity than the insulator **210**. In the case where a material with a low permittivity is used for an interlayer film, the parasitic capacitance generated between wirings can be reduced.

(511) For example, for the insulator **280** functioning as an interlayer film, a single layer or stacked layers of any of insulators such as silicon oxide, silicon oxynitride, silicon nitride oxide, aluminum oxide, hafnium oxide, tantalum oxide, zirconium oxide, lead zirconate titanate (PZT), strontium titanate (SrTiO₃), and (Ba,Sr)TiO₃ (BST) can be used. Alternatively, aluminum oxide, bismuth oxide, germanium oxide, niobium oxide, silicon oxide, titanium oxide, tungsten oxide, yttrium oxide, or zirconium oxide may be added to the insulator, for example. Alternatively, the insulator may be subjected to nitriding treatment. Silicon oxide, silicon oxynitride, or silicon nitride may be stacked over the insulator.

(512) Furthermore, the conductor **252a**, the conductor **252b**, the conductor **252c**, and the conductor **252d** are placed in the openings formed in the insulator **280** and the like. Note that the top surfaces of the conductor **252a**, the conductor **252b**, the conductor **252c**, and the conductor **252d** may be substantially level with the top surface of the insulator **280**.

(513) The conductor **252a** is in contact with the region **233** functioning as one of a source region and a drain region of the transistor **202** through the opening formed in the insulator **280** and the insulator **274**. Since the resistance of the region **233** is reduced, the contact resistance between the conductor **252a** and the region **233** can be reduced. The conductor **252b** is in contact with the

conductor **130** that is one electrode of the capacitor **101** through the opening formed in the insulator **280**. The conductor **252c** is in contact with the conductor **260** functioning as the first gate electrode of the transistor **202** through the opening formed in the insulator **280**, the insulator **274**, the insulator **271**, and the insulator **270**. The conductor **252d** is in contact with the conductor **207** through the opening formed in the insulator **280**, the insulator **274**, the insulator **222**, and the insulator **220**, and is electrically connected to the conductor **205** functioning as the second gate electrode of the transistor **202** through the conductor **209**.

(514) Here, the conductor **252a** is in contact with at least the top surface of the oxide **230**, preferably also in contact with the side surface of the oxide **230**. It is particularly preferable that the conductor **252a** be in contact with one or both of the side surface on the C side and the side surface on the D side, which intersect with the channel width direction of the oxide **230**. Moreover, the conductor **252a** may be in contact with the side surface on the A side, which intersects with the channel length direction of the oxide **230**. When the conductor **252a** is in contact with the side surface of the oxide **230** in addition to the top surface of the oxide **230** as described above, the contact area of the contact portion of the conductor **252a** and the oxide **230** can be increased without an increase in the area of the top surface of the contact portion, so that the contact resistance between the conductor **252a** and the oxide **230** can be reduced. Accordingly, miniaturization of the source electrode and the drain electrode of the transistor can be achieved and, in addition, the on-state current can be increased.

(515) For the conductor **252**, a conductive material containing tungsten, copper, or aluminum as its main component is preferably used. The conductor **252** may have a stacked-layer structure, and for example, stacked layers of titanium, titanium nitride, and any of the above conductive materials may be used.

(516) In the case where the conductor **252** has a stacked-layer structure, a conductive material having a function of inhibiting passage of impurities such as water and hydrogen is preferably used for a conductor in contact with the insulator **274** and the insulator **280**, as in the conductor **205a** or the like. For example, tantalum, tantalum nitride, titanium, titanium nitride, ruthenium, or ruthenium oxide is preferably used. The conductive material having a function of inhibiting passage of impurities such as water and hydrogen may be a single layer or stacked layers. When the conductive material is used, impurities such as hydrogen and water can be inhibited from entering the oxide **230** through the conductor **252** from a layer above the insulator **280**.

(517) An insulator having a function of inhibiting passage of impurities such as water and hydrogen may be provided in contact with the inner wall of the opening in the insulator **274** and the insulator **280** in which the conductor **252** is embedded. As such an insulator, an insulator which can be used as the insulator **210**, such as aluminum oxide is preferably used, for example. Accordingly, impurities such as hydrogen and water can be inhibited from entering the oxide **230** through the conductor **252** from the insulator **280** or the like. Moreover, for example, the insulator can be deposited with good coverage by using an ALD method or a CVD method.

(518) Although not illustrated, conductors functioning as wirings may be placed in contact with the top surface of the conductor **252**. A conductive material containing tungsten, copper, or aluminum as its main component is preferably used for the conductors functioning as the wirings.

(519) <Structure Example 4 of Semiconductor Device>

(520) FIG. 25(A), FIG. 25(B), FIG. 25(C), and FIG. 25(D) are a top view and cross-sectional views of a transistor **204** of one embodiment of the present invention, a capacitor **102**, and the periphery of the transistor **204**. Note that in this specification, a semiconductor device including one capacitor and at least one transistor is referred to as a cell.

(521) A cell **602** illustrated in FIG. 25 includes the transistor **204** and the capacitor **102**, and is different from the transistor **202** described above in the structures of the conductor **203** and the conductor **205**. In addition, the shapes of the insulator **250**, the conductor **260**, the insulator **270**, and the insulator **271** are different from those of the transistor **202**.

(522) The conductor **203** and the conductor **205** are provided over the conductor **209** and the insulator **212**. The conductor **203** and the conductor **205** can be formed using a material and a method similar to those for the conductor **209**. However, in the case where a defect in the shape of the conductor **209** might be caused in processing the conductor **203** and the conductor **205**, a material different from that for the conductor **209** is preferably used for the conductor **203** and the conductor **205**. The insulator **216** can be formed using a material and a method similar to those for the insulator **212**.

(523) The side surfaces of the insulator **250**, the conductor **260**, the insulator **270**, and the insulator **271** are tapered. At least the side surfaces of the insulator **250** and the conductor **260** are provided with the insulator **272** and the insulator **273**, the side surfaces of the insulator **250** and the conductor **260** are preferably perpendicular to the surface of the substrate or the surfaces of the insulator **220** and the insulator **222**. In contrast, when an insulating film to be the insulator **272** and the insulator **273** is formed, the side surfaces of the insulator **250** and the conductor **260** are preferably tapered because coverage is improved. The taper angle of the side surfaces of the insulator **250** and the conductor **260** can be adjusted as appropriate in consideration of the ease of the fabrication in the process.

(524) An example is shown in which the cell **602** illustrated in FIG. **25** is different from the transistor **202** in the structures of the conductor **203** and the conductor **205** and the shapes of the insulator **250**, the conductor **260**, the insulator **270**, and the insulator **271**; however, either the structures of the conductor **203** and the conductor **205** or the shapes of the insulator **250**, the conductor **260**, the insulator **270**, and the insulator **271** may be different from those of the transistor **202**.

(525) <Structure Example 5 of Semiconductor Device>

(526) FIG. **26(A)**, FIG. **26(B)**, FIG. **26(C)**, and FIG. **26(D)** are a top view and cross-sectional views of a transistor **206** of one embodiment of the present invention, a capacitor **103**, and the periphery of the transistor **206**. Note that in this specification, a semiconductor device including one capacitor and at least one transistor is referred to as a cell.

(527) A cell **603** illustrated in FIG. **26** includes the transistor **206** and the capacitor **103**, and is different from the transistor **202** described above in that the oxide **230d** is not etched and remains over the region **231** and the region **233**.

(528) In that case, an end portion of the oxide **230c** is covered with the oxide **230d**, so that entry of impurities into the oxide **230**, release of oxygen from the oxide **230**, or the like can be inhibited, which is preferable.

(529) Alternatively, the conductor **203** and the conductor **205** may have a structure illustrated in FIG. **25**. Alternatively, the insulator **250**, the conductor **260**, the insulator **270**, and the insulator **271** may have a shape illustrated in FIG. **25**.

(530) <Structure of Cell Array>

(531) Here, FIG. **27** and FIG. **28** illustrate examples of a cell array of this embodiment. The cells **601** each including the transistor **202** and the capacitor **101**, which are illustrated in FIG. **23**, and transistors **300** electrically connected to the cells **601** are arranged in a matrix, for example, whereby a cell array can be formed.

(532) FIG. **27** is a circuit diagram showing one embodiment of a cell array in which the cells **601** illustrated in FIG. **23** and the transistors **300** electrically connected to the cells **601** are arranged in a matrix. FIG. **28(A)** is a circuit diagram of a circuit **620** extracted from the cell array, and FIG. **28(B)** is a schematic cross-sectional view of the cell **601** and the transistor **300** and corresponds to the cell array.

(533) A transistor provided on a semiconductor substrate can be used as the transistor **300**. The semiconductor substrate preferably includes a semiconductor such as a silicon-based semiconductor, and preferably contains single crystal silicon. Alternatively, a semiconductor substrate containing Ge (germanium), SiGe (silicon germanium), GaAs (gallium arsenide), GaAlAs

(gallium aluminum arsenide), or the like may be used. In this case, the transistor **300** is of either a p-channel type or an n-channel type. Like the transistor **202**, the transistor **300** can be a transistor including an oxide semiconductor.

(534) In FIG. **27**, one of the source and the drain of each of the transistors **202** included in the cells **601** which are adjacent in the row direction is electrically connected to common wirings (**S01**, **502**, and **S03**). Furthermore, the wirings are also electrically connected to one of the source and the drain of each of the transistors **202** included in the cells arranged in the column direction. In contrast, the first gates of the transistors **202** included in the cells **601** which are adjacent in the row direction are electrically connected to different wirings WL (**WL01** to **WL06**). Furthermore, the second gates of the transistors **202** included in the cells **601** may be electrically connected to a transistor **400**. By a potential applied to the second gate of the transistor **202** through the transistor **400**, the threshold voltage of the transistor can be controlled.

(535) The first electrode of the capacitor **101** included in the cell **601** is electrically connected to the other of the source and the drain of the transistor **202** and a gate of the transistor **300**. At this time, the first electrode of the capacitor **101** is formed using part of components of the transistor **202** in some cases. In addition, the second electrode of the capacitor **101** included in the cell **601** is electrically connected to a wiring PL. The potential of the wiring PL electrically connected to the second electrode of the capacitor **101** may be the same or different between the cells **601**. For example, the wiring PL may have a common potential per column or may have a common potential per row.

(536) One of a source and a drain of the transistor **300** is electrically connected to a wiring SL (**SL01** to **SL06**), and the other of the source and the drain of the transistor **300** is electrically connected to a wiring BL (**BL01** to **BL06**).

(537) As illustrated in FIG. **28(B)**, a cell **601a** includes a transistor **202a** and a capacitor **101a**, and is electrically connected to a gate of a transistor **300a**. A cell **601b** includes a transistor **202b** and a capacitor **101b**, and is electrically connected to a gate of a transistor **300b**.

(538) One of a source and a drain of the transistor **202a** and one of a source and a drain of the transistor **202b** are electrically connected to the **502**.

(539) One of the source and the drain of the transistor **202** is electrically connected to the gate of the transistor **300** and a first electrode of the capacitor **101a**, whereby a desired potential can be applied to and retained in the gate of the transistor **300**. The transistor **202** including an oxide semiconductor in a channel formation region has an extremely low leakage current in a non-conduction state. Thus, the potential applied to the gate electrode of the transistor **300** can be retained for a long time.

(540) Such a cell array can be used for a memory device or an arithmetic circuit.

(541) [Transistor **400**]

(542) FIG. **29** is a schematic cross-sectional view illustrating one embodiment of the transistor **400**. The transistor **400** may have a structure different from that of the transistor **202**.

(543) The transistor **400** is preferably formed using the same material as that for the transistor **202**.

(544) A conductor **409** can be formed using a material similar to that for the conductor **209** in the same step as the conductor **209**. A conductor **403** and a conductor **405** can be formed using a material similar to that for the conductor **203** and the conductor **205** in the same step as those conductors. The conductor **405** can function as a second gate electrode of the transistor **400**.

(545) An oxide **430a**, an oxide **430b**, an oxide **430c**, and an oxide **430d** can be formed using a material similar to that for the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d** in the same step as those oxides. In the transistor **400**, part of the oxide **430d** functions as a channel formation region, and the oxide **430a**, the oxide **430b**, the oxide **430c**, and the oxide **430d** each include, like the oxide **230**, a low-resistance region functioning as a source region or a drain region. Furthermore, a contact region having a lower resistance is preferably provided in each of the oxide **430a**, the oxide **430b**, and the oxide **430c**.

(546) An insulator **450a** and an insulator **450b** can be formed using a material similar to that for the insulator **250a** and the insulator **250b** in the same step as those insulators, and an insulator **450** including the insulator **450a** and the insulator **450b** can function as a gate insulating film. A conductor **460a** and a conductor **460b** can be formed using a material similar to that for the conductor **260a** and the conductor **260b** in the same step as those conductors, and a conductor **460** including the conductor **460a** and the conductor **460b** can function as a first gate electrode.

(547) An insulator **470** can be formed using a material similar to that for the insulator **270** in the same step as the insulator **270**. An insulator **471** can be formed using a material similar to that for the insulator **271** in the same step as the insulator **271**. An insulator **472** can be formed using a material similar to that for the insulator **272** in the same step as the insulator **272**. An insulator **473** can be formed using a material similar to that for the insulator **273** in the same step as the insulator **273**.

(548) Opening portions are provided in the insulator **280** and the insulator **274**, and a conductor **452a** and a conductor **452b**, which are connected to the oxide **430**, are placed.

(549) In the transistor **400**, one of a source region and a drain region is electrically connected to the conductor **403** through an opening provided in the oxide **430a**, the insulator **224**, the insulator **222**, and the insulator **220**. The conductor **403** is electrically connected to the conductor **405** functioning as the second gate electrode through the conductor **409**. One of the source region and the drain region is electrically connected to the conductor **460** functioning as the second gate electrode through the conductor **452b**. In other words, one of the source region and the drain region, the first gate electrode, and the second gate electrode are electrically connected to each other, whereby a diode connection is formed in the transistor **400**.

(550) One of the source and the drain of the diode-connected transistor **400** is electrically connected to the second gate electrode of the transistor **202** through the conductor **409**, the conductor **209**, and the like. Thus, the potential of the second gate electrode of the transistor **202** can be controlled by the transistor **400**. A channel formation region is provided in the oxide **430d**; therefore, the transistor **400** has an extremely low leakage current in a non-conduction state. Thus, when a negative potential is applied to the second gate electrode of the transistor **202**, for example, the potential of the second gate electrode of the transistor **202** can be retained for a long time even without supply of power to the transistor **400**.

(551) The transistor **400** is not necessarily provided in each cell **601** and a plurality of cells may be provided with a smaller number of transistors **400** than that of the cells. For example, in a cell array in which the cells **601** are arranged in a matrix, one transistor **400** may be provided in the cell array, one transistor **400** may be provided in each row, or one transistor **400** may be provided in each column.

(552) <Method for Manufacturing Semiconductor Device>

(553) Next, a method for manufacturing a semiconductor device including the transistor **202** of the present invention will be described with reference to FIG. **30** to FIG. **50**. In FIG. **30** to FIG. **50**, (A) of each drawing is a top view. Moreover, (B) of each drawing is a cross-sectional view corresponding to a portion denoted by dashed-dotted line A-B in (A). Furthermore, (C) of each drawing is a cross-sectional view corresponding to a portion denoted by dashed-dotted line C-D in (A). Furthermore, (D) of each drawing is a cross-sectional view corresponding to a portion denoted by dashed-dotted line E-F in (A).

(554) In the method for manufacturing the semiconductor device of this embodiment, materials, a manufacturing method, and a manufacturing apparatus similar to those in Embodiment 1 can be used for components with the same reference numerals as those in the method for manufacturing the semiconductor device in Embodiment 1. Unless otherwise specified, the components formed in this embodiment can obtain structural characteristics and effects similar to those of the components described in Embodiment 1, and description thereof is omitted.

(555) First, a substrate (not illustrated) is prepared, and the insulator **208** is deposited over the

substrate. The insulator **208** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(556) In this embodiment, as the insulator **208**, silicon oxide is deposited by a CVD method.

(557) Next, the insulator **210** is formed over the insulator **208**. In this embodiment, aluminum oxide is deposited as the insulator **210** by a sputtering method. The insulator **210** may have a multilayer structure. For example, aluminum oxide may be deposited by a sputtering method and aluminum oxide may be deposited over the aluminum oxide by an ALD method. Alternatively, aluminum oxide may be deposited by an ALD method and aluminum oxide may be deposited over the aluminum oxide by a sputtering method.

(558) Then, a conductive film **209A** is formed over the insulator **210**. The conductive film **209A** can be formed by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. In this embodiment, as the conductive film **209A**, tungsten is deposited by a sputtering method. Note that as the conductive film **209A**, a conductor such as aluminum or copper can be used as well as tungsten. The conductive film **209A** may have a stacked-layer structure, and a conductor containing titanium or tantalum may be stacked over the conductor. For example, a metal nitride such as titanium nitride or tantalum nitride can be stacked over the conductor.

(559) Next, the masks **262** are formed over the conductive film **209A** by a lithography method (see FIG. **30**).

(560) Then, the conductive film **209A** is processed using the masks **262**, so that the conductor **209** is formed (see FIG. **31**).

(561) For the processing, a dry etching method or a wet etching method can be employed. A dry etching method is suitable for microfabrication.

(562) As a dry etching apparatus, a dry etching apparatus such as a CCP etching apparatus or an ICP etching apparatus can be used.

(563) In the case where a hard mask is used for etching of the conductive film **209A**, the etching treatment may be performed after the resist mask used for formation of the hard mask is removed or with the resist mask left. In the latter case, the resist mask is removed during the etching in some cases. The hard mask may be removed by etching after the etching of the conductive film. In contrast, the hard mask does not need to be removed in the case where the hard mask material does not affect the following process or can be utilized in the following process.

(564) Next, an insulating film **212A** is formed over the insulator **210** and the conductor **209** (see FIG. **32**). The insulating film **212A** can be formed by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. In this embodiment, as the insulating film **212A**, silicon oxide is formed by a CVD method.

(565) Next, part of the insulating film **212A** is removed by CMP treatment, so that the conductor **209** is exposed. As a result, the insulator **212** remains between the conductors **209** and around these conductors. In this way, the insulator **212** and the conductor **209** with flat top surfaces can be formed (see FIG. **33**). Note that by the CMP treatment, the conductor **209** is partly removed in some cases.

(566) Next, the insulator **216** is deposited over the insulator **212** and the conductor **209**. The insulator **216** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. In this embodiment, as the insulator **216**, silicon oxide is deposited by a CVD method.

(567) Then, openings are formed in the insulator **216**. Examples of the openings include grooves and slits. Regions where the openings are formed may be referred to as opening portions. The openings can be formed by wet etching; however, dry etching is preferable for microfabrication. In the case where openings are formed in the insulator **216**, the conductor **209** may be used as an etching stopper film in forming the groove by etching the insulator **216**.

(568) After formation of the openings, a conductive film to be the conductor **203a** and the conductor **205a** is deposited. The conductive film desirably includes a conductor that has a function

of inhibiting passage of oxygen. For example, tantalum nitride, tungsten nitride, or titanium nitride can be used. Alternatively, a stacked film including tantalum, tungsten, titanium, molybdenum, aluminum, copper, or a molybdenum-tungsten alloy can be used. A conductor to be the conductor **203a** and the conductor **205a** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(569) In this embodiment, as the conductive film to be the conductor **203a** and the conductor **205a**, tantalum nitride or a film in which titanium nitride is stacked over tantalum nitride is deposited by a sputtering method. Even when a metal that is easily diffused, such as copper, is used for the conductor **203b** and the conductor **205b** to be described later, the use of such a metal nitride as the conductor **203a** and the conductor **205a** can prevent the metal from being diffused to the outside of the conductor **203a** and the conductor **205a**.

(570) Next, a conductive film to be the conductor **203b** and the conductor **205b** is deposited over the conductive film to be the conductor **203a** and the conductor **205a**. The conductive film can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. In this embodiment, as the conductive film to be the conductor **203b** and the conductor **205b**, a low-resistant conductive material such as tungsten or copper is deposited.

(571) Next, by CMP treatment, the conductive film to be the conductor **203a** and the conductor **205a** and the conductive film to be the conductor **203b** and the conductor **205b** are partly removed to expose the insulator **216**. As a result, the conductive film to be the conductor **203a** and the conductor **205a** and the conductive film to be the conductor **203b** and the conductor **205b** remain only in the opening portions. Thus, the conductor **203** including the conductor **203a** and the conductor **203b**, which have a flat top surface, and the conductor **205** including the conductor **205a** and the conductor **205b**, which have a flat top surface, can be formed (see FIG. 34). Note that the insulator **216** is partly removed by the CMP treatment in some cases.

(572) Next, the insulator **220**, the insulator **222**, and the insulator **224** are deposited over the insulator **216**, the conductor **203**, and the conductor **205**. The insulator **220**, the insulator **222**, and the insulator **224** can be formed using a method and a material similar to those in Embodiment 1 (see FIG. 34).

(573) Subsequently, heat treatment is preferably performed. For the heat treatment, the method described in Embodiment 1 can be used. By the above heat treatment, impurities such as hydrogen and water in the insulator **224** can be removed, for example. Note that first heat treatment is not necessarily performed in some cases.

(574) This heat treatment can also be performed after deposition of the insulator **220** and after deposition of the insulator **222**. Although the heat treatment can be performed under the above-described heat treatment conditions, heat treatment after deposition of the insulator **220** is preferably performed in an atmosphere containing nitrogen.

(575) In this embodiment, as the heat treatment, treatment is performed in a nitrogen atmosphere at 400° C. for one hour after deposition of the insulator **224**.

(576) Next, the oxide film **230A** to be the oxide **230a** is formed over the insulator **224**.

(577) The oxide film **230A** can be formed using a method and a material similar to those in Embodiment 1.

(578) Next, an opening reaching the conductor **203** is formed in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide film **230A** by a lithography method. First, the mask **263** is formed over the oxide film **230A** (see FIG. 34). The mask **263** used for forming the opening may be a resist mask or a hard mask.

(579) Next, the insulator **220**, the insulator **222**, the insulator **224**, and the oxide film **230A** are processed using the mask **263** to expose the surface of the conductor **203**, so that the opening is formed (see FIG. 35). For the processing, a dry etching method or a wet etching method can be employed. A dry etching method is suitable for microfabrication. Note that the insulator **220**, the insulator **222**, and the insulator **224** are processed through the oxide film **230A**. Specifically, when

the surface of the conductor **203** is partly exposed, a mask formed of a resist mask, a hard mask, or the like is formed over the oxide film **230A**, and then the insulator **220**, the insulator **222**, the insulator **224**, and the oxide film **230A** are processed. In other words, the mask is not formed on a surface of the insulator (the insulator **220**, the insulator **222**, and the insulator **224**) functioning as the gate insulating film. Therefore, the mask is not attached to the surface of the insulator functioning as the gate insulating film; thus, the gate insulating film can be prevented from being contaminated and damaged by an impurity in the resist mask and the like, a component in the hard mask, and components in plasma and a chemical solution used for removal of the mask. Through such a process, a method for manufacturing a highly reliable semiconductor device can be provided.

(580) Next, the oxide film **230B** and the oxide film **230C** are formed over the oxide film **230A** (see FIG. **36**). At this time, the oxide film **230B** and the oxide film **230C** are also formed in the opening and electrically connected to the conductor **203** through the opening. When the oxide **230b** and the oxide **230c** are connected to the conductor **203** without through the oxide **230a**, the series resistance and the contact resistance can be reduced. With such a structure, a semiconductor device with favorable electrical characteristics can be obtained. Specifically, a transistor with an increased on-state current and a semiconductor device including the transistor are obtained.

(581) The oxide film **230B** and the oxide film **230C** can be formed by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(582) After the formation of the oxide film **230B**, the oxide film **230C** is preferably formed successively without exposure to an air atmosphere. When a multi-chamber deposition apparatus is used for the formation of the oxide film **230B** and the formation of the oxide film **230C**, the oxide film **230C** can be formed over the oxide film **230B** without exposure of the surface of the oxide film **230B** to an air atmosphere. By performing the formation of the oxide film **230B** and the formation of the oxide film **230C** successively, contamination of the interface between the oxide film **230B** and the oxide film **230C** can be prevented, and the semiconductor device using such oxide films can have favorable characteristics and high reliability.

(583) In the case where the oxide film **230B** and the oxide film **230C** are formed by a sputtering method, for example, oxygen or a mixed gas of oxygen and a rare gas is used as a sputtering gas. By increasing the proportion of oxygen in the sputtering gas, the amount of excess oxygen in the oxide film to be deposited can be increased. In the case where the oxide films are formed by a sputtering method, the above-described In-M-Zn oxide target can be used.

(584) In the case where the oxide film **230B** and the oxide film **230C** are formed by a sputtering method and the proportion of oxygen in the sputtering gas is higher than or equal to 1% and lower than or equal to 30%, preferably higher than or equal to 5% and lower than or equal to 20% an oxygen-deficient oxide semiconductor is formed. A transistor including an oxygen-deficient oxide semiconductor can have relatively high field-effect mobility.

(585) In this embodiment, the oxide film **230B** is deposited using a target of In:Ga:Zn=1:1:1 [atomic ratio] by a sputtering method, and the oxide film **230C** is deposited using a target of In:Ga:Zn=4:2:4.1 [atomic ratio] by a sputtering method. The oxide film **230B** and the oxide film **230C** are successively formed without exposure to an air atmosphere by using a multi-chamber sputtering apparatus. Note that the oxide films are preferably formed by appropriate selection of deposition conditions and an atomic ratio to have characteristics required for the oxide **230**.

(586) Next, heat treatment may be performed. For the heat treatment, the above-described heat treatment conditions can be used. By the heat treatment, impurities such as water and hydrogen in the oxide film **230A**, the oxide film **230B**, and the oxide film **230C** can be removed, for example. In this embodiment, treatment is performed in a nitrogen atmosphere at 400° C. for one hour, and treatment is successively performed in an oxygen atmosphere at 400° C. for one hour.

(587) Next, the oxide film **230A**, the oxide film **230B**, and the oxide film **230C** are processed into island shapes to form the oxide **230a**, the oxide **230b**, and the oxide **230c** (see FIG. **37**).

(588) As illustrated in FIG. 37(A) and FIG. 37(D), the oxide **230a**, the oxide **230b**, and the oxide **230c** are each preferably formed to have a wider width in the E-F direction than the opening in the region overlapping with the opening formed in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**. Therefore, the widths of the oxide **230a**, the oxide **230b**, and the oxide **230c** in the E-F direction in that region may be wider than the widths of the oxide **230a**, the oxide **230b**, and the oxide **230c** in the C-D direction in a region where a channel is formed or a region on the A side. With such a structure, contact between the oxides **230b** and **230c** and the conductor **203** can be assured. Furthermore, the area of the capacitor **101** can be increased, and an increase in the capacity of the capacitor **101** can be expected.

(589) Note that in the above step, the insulator **224** may be processed into an island shape. Furthermore, the insulator **224** may be subjected to half-etching. In the case where the insulator **224** is subjected to half-etching, the insulator **224** remains also under the oxide **230d** to be formed in a later step. Note that the insulator **224** can be processed into an island shape when the conductive film **260A** and the conductive film **260B** or the insulating film **272A** is processed in a later step. In this case, the insulator **222** may be used as an etching stopper film.

(590) Here, the oxide **230a**, the oxide **230b**, and the oxide **230c** are formed to at least partly overlap with the conductor **205**. It is preferable that the side surface of the oxide **230b** and a side surface of the oxide **230c** be on the same plane as the side surface of the oxide **230a**. It is also preferable that the side surfaces of the oxide **230a**, the oxide **230b**, and the oxide **230c** be substantially perpendicular to the insulator **222**. At this time, the end portion of the oxide **230b** and the end portion of the oxide **230c** are substantially aligned with the end portion of the oxide **230a**. When the side surfaces of the oxide **230a**, the oxide **230b**, and the oxide **230c** are substantially perpendicular to the insulator **222**, a plurality of transistors **202** can be provided in a small area with high density. Note that an angle formed by the side surfaces of the oxide **230a**, the oxide **230b**, and the oxide **230c** and the top surface of the insulator **222** may be an acute angle. In that case, the angle formed by the side surfaces of the oxide **230a**, the oxide **230b**, and the oxide **230c** and the top surface of the insulator **222** is preferably larger.

(591) There is a curved surface between the side surfaces of the oxide **230a**, the oxide **230b**, and the oxide **230c** and the top surface of the oxide **230c**. That is, an end portion of the side surface and an end portion of the top surface are preferably curved (hereinafter also referred to as a round shape). The radius of curvature of the curved surface at the end portions of the oxide **230a**, the oxide **230b**, and the oxide **230c** is greater than or equal to 3 nm and less than or equal to 10 nm, preferably greater than or equal to 5 nm and less than or equal to 6 nm, for example.

(592) Note that when the end portions are not angular, the coverage with films in the later deposition process is improved.

(593) Note that processing of the oxide films and washing for removing impurities attached at the time of the processing can be performed by the methods described in Embodiment 1.

(594) Next, heat treatment may be performed. As the conditions for the heat treatment, the above-described heat treatment conditions can be used.

(595) Next, an oxide film **230D** to be the oxide **230d** is deposited over the insulator **224**, the oxide **230a**, the oxide **230b**, and the oxide **230c** (see FIG. 38).

(596) The oxide film **230D** can be formed by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. The oxide film **230D** is deposited by a deposition method similar to that of the oxide film **230A**, the oxide film **230B**, or the oxide film **230C** in accordance with characteristics required for the oxide **230d**. In this embodiment, the oxide film **230D** is deposited using a target of In:Ga:Zn=1:3:4 [atomic ratio] by a sputtering method.

(597) The oxide film **230D** may be processed into an island shape as illustrated in FIG. 39. When the oxide film **230D** is processed before the formation of the insulator **250** and the conductor **260**, part of the oxide film **230D** positioned below the insulator **250** and the conductor **260**, which are formed in a later process, can be removed. Thus, the oxide film **230D** for adjacent cells **601** is

divided and leakage through the oxide film **230D** between the cells **601** can be prevented, which is preferable.

(598) The oxide film **230D** can be processed by dry etching or wet etching. The method used for processing the oxide film **230A**, the oxide film **230B**, and the oxide film **230C** may also be used.

(599) Then, the insulating film **250A**, an insulating film **250B**, the conductive film **260A**, the conductive film **260B**, the insulating film **270A**, and the insulating film **271A** are formed sequentially over the insulator **224** and the oxide film **230D** (see FIG. **40**).

(600) The insulating film **250A** and the insulating film **250B** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like.

(601) In this embodiment, silicon oxynitride is formed by a CVD method as the insulating film **250A**, and aluminum oxide is formed by a sputtering method as the insulating film **250B**. The insulating film **250A** has a thickness of greater than or equal to 1 nm and less than or equal to 20 nm, preferably greater than or equal to 5 nm and less than or equal to 10 nm. The insulating film **250B** has a thickness of greater than or equal to 1 nm and less than or equal to 20 nm, preferably greater than or equal to 5 nm and less than or equal to 10 nm. The insulating film **250B** is preferably formed by a sputtering method in an atmosphere containing oxygen, in which case, a larger amount of oxygen, that is, excess oxygen can be contained in the insulating film **250A**.

(602) Furthermore, heat treatment may be performed. For the heat treatment, the above-described heat treatment conditions can be used. The heat treatment can reduce the moisture concentration and the hydrogen concentration in the insulating film **250A** and the insulating film **250B**.

(603) The conductive film **260A** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. In this embodiment, as the conductive film **260A**, titanium nitride is formed by a sputtering method.

(604) The conductive film **260B** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. When a low-resistance metal film is stacked as the conductive film **260B**, a transistor with a low driving voltage can be provided. In this embodiment, as the conductive film **260B**, tungsten is formed by a sputtering method.

(605) Subsequently, heat treatment can be performed. For the heat treatment, the above-described heat treatment conditions can be used. Note that the heat treatment is not necessarily performed in some cases. In this embodiment, the treatment is performed in a nitrogen atmosphere at 400° C. for one hour.

(606) The insulating film **270A** and the insulating film **271A** can be formed using a method and a material similar to those in Embodiment 1.

(607) The insulator **271** functions as a hard mask. The provision of the insulator **271** makes it possible for a side surface of the insulator **250a**, a side surface of the insulator **250b**, the side surface of the conductor **260a**, the side surface of the conductor **260b**, and the side surface of the insulator **270** to be formed substantially perpendicular to the substrate.

(608) Next, the insulating film **271A** is etched to form the insulator **271**. Then, using the insulator **271** as a mask, the insulating film **250A**, the insulating film **250B**, the conductive film **260A**, the conductive film **260B**, and the insulating film **270A** are etched to form the insulator **250** (the insulator **250a** and the insulator **250b**), the conductor **260** (the conductor **260a** and the conductor **260b**), and the insulator **270** (see FIG. **41**). Note that after the processing, the following process may be performed without removal of the hard mask. The hard mask can also function as a hard mask used for adding a dopant, which is to be performed in the following process.

(609) An upper portion of the oxide film **230D** in a region not overlapping with the insulator **250** may be etched by the above etching. In that case, the oxide film **230D** may be thicker in a region overlapping with the insulator **250** than in the region not overlapping with the insulator **250**.

(610) A region of the insulator **224** not overlapping with the oxide film **230D** may be etched by the above etching. In this case, the insulator **222** is exposed in a region not overlapping with the oxide film **230D** or the conductor **260**.

(611) Subsequently, heat treatment can be performed. For the heat treatment, the above-described heat treatment conditions can be used. Note that the heat treatment is not necessarily performed in some cases. In this embodiment, the treatment is performed in a nitrogen atmosphere at 400° C. for one hour.

(612) Next, the insulating film **272A** is deposited to cover the oxide film **230D**, the insulator **250**, the conductor **260**, the insulator **270**, and the insulator **271** (see FIG. 42).

(613) Next, a rare gas is added to the oxide **230** using the insulator **250**, the conductor **260**, the insulator **270**, and the insulator **271**, which are covered with the insulating film **272A**, as masks.

(614) For the addition of the rare gas, for example, an ion implantation method by which an ionized source gas is subjected to mass separation and then added, an ion doping method by which an ionized source gas is added without mass separation, a plasma immersion ion implantation method, or plasma treatment can be used. By addition of a rare gas, the region **234** and the region **232** are provided in the oxide **230** (see FIG. 42).

(615) Next, an insulating film **273A** is deposited to cover the insulating film **272A** (see FIG. 43). For the insulating film **273A**, a material with a low permittivity is preferably used, and a material similar to that for the insulator **212** and the insulator **216** can be used.

(616) Next, the insulating film **273A** and the insulating film **272A** are subjected to anisotropic etching treatment, whereby the insulator **272** functioning as a barrier and the insulator **273** functioning as a sidewall are formed in contact with the side surfaces of the insulator **250**, the conductor **260**, and the insulator **270** (see FIG. 44). Dry etching treatment is preferably performed as the anisotropic etching treatment. In this manner, the insulator **272** and the insulator **273** can be formed in a self-aligned manner.

(617) The insulator **271** is formed over the insulator **270** here, whereby the insulator **270** can be left even when the insulating film **273A** and the insulating film **272A** in a portion above the insulator **270** are removed. The height of a structure body composed of the insulator **250**, the conductor **260**, the insulator **270**, and the insulator **271** is made greater than the total height of the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide film **230D**, whereby the insulating film **273A** and the insulating film **272A**, which are deposited on the side surfaces of the oxide **230a**, the oxide **230b**, and the oxide **230c** with the oxide film **230D** therebetween, can be removed. Furthermore, when the end portions of the oxide **230a**, the oxide **230b**, and the oxide **230c** have a round shape, time taken to remove the insulating film **273A** and the insulating film **272A**, which are deposited on the side surfaces of the oxide **230a**, the oxide **230b**, and the oxide **230c** with the oxide film **230D** therebetween, can be shortened, leading to easier formation of the insulator **272** and the insulator **273**.

(618) Next, the oxide film **230D** is etched using the insulator **250**, the conductor **260**, the insulator **270**, the insulator **271**, the insulator **272**, and the insulator **273** as masks to remove part of the oxide film **230D**, so that the oxide **230d** is formed (see FIG. 45). Note that through the present process, the top surface and the side surfaces of the oxide **230c** and the side surfaces of the oxide **230a** and the oxide **230b** are partly removed in some cases.

(619) Here, the region **231** may be formed in the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d**. The region **231** is a region whose resistance is reduced by addition of a metal atom such as indium or impurities to metal oxides provided as the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d**. Note that each region **231** has higher conductivity than at least the oxide **230b** in the region **234**.

(620) In order to reduce the resistance of the region **231** and the region **232**, a dopant which is at least one of a metal atom such as indium, a rare gas such as helium or argon, and an impurity such as hydrogen and nitrogen is added, for example.

(621) Note that a dopant and an addition method similar to those in Embodiment 1 can be used for addition of a dopant.

(622) Alternatively, a dopant may be added by plasma treatment. In that case, the plasma treatment

can be performed with a plasma CVD apparatus, a dry etching apparatus, or an ashing apparatus to add a dopant to the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d**.

(623) Furthermore, in the case where an impurity is added as a dopant, a film containing a dopant may be formed in contact with the oxide **230**. For example, the insulator **274** containing hydrogen, boron, carbon, nitrogen, fluorine, or phosphorus as a dopant is deposited in contact with the oxide **230** positioned outward from the oxide **230d**, the insulator **272**, and the insulator **273**, whereby the region **231** is formed (see FIG. **46**). Owing to the deposition of the insulator **274** or the heat treatment after the deposition, the resistance of the region **231** is reduced. It is considered that the dopant in the insulator **274** is diffused into the region **231** and the resistance of the region is reduced. The dopant in the insulator **274** may also be diffused into the region **232**, and the resistance of the region **232** may become lower than the resistance reduced by the above-described addition of the rare gas.

(624) When the indium content in the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d** is increased, the carrier density can be increased and the resistance can be reduced.

Accordingly, a metal element that improves the carrier density of the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d**, such as indium, can be used as a dopant.

(625) That is, when the content of a metal atom such as indium in the oxide **230a**, the oxide **230b**, the oxide **230c**, and the oxide **230d** is increased in the region **231** and the region **232**, the electron mobility can be increased and the resistance can be reduced.

(626) In that case, the atomic ratio of indium to the element M at least in the region **231** is larger than the atomic ratio of indium to the element M in the region **234**.

(627) When the region **232** is provided in the transistor **202**, a high-resistance region is not formed between the region **231** functioning as the source region or the drain region and the region **234** where a channel is formed, so that the on-state current and the mobility of the transistor can be increased. Since the gate does not overlap with the source region and the drain region in the channel length direction owing to the region **232**, formation of unnecessary capacitance can be inhibited. Furthermore, leakage current in a non-conduction state can be reduced by including the region **232**.

(628) Thus, by appropriately selecting the areas of the region **231a** and the region **231b**, a transistor having electrical characteristics required in the circuit design can be easily provided.

(629) In this embodiment, the insulator **274** is deposited to cover the insulator **224**, the oxide **230**, the insulator **271**, the insulator **272**, and the insulator **273** (see FIG. **46**).

(630) The insulator **274** can be formed using a method and a material similar to those in Embodiment 1. Accordingly, oxygen vacancies are formed mainly in regions not overlapping with the insulator **250**, of the oxide **230c** and the oxide **230d** and the oxygen vacancies and impurity elements such as nitrogen and hydrogen are bonded to each other, leading to an increase in carrier density. In this manner, the region **231a** and the region **231b** with reduced resistance can be formed.

(631) As described in Embodiment 1, the insulator **274** may have a single-layer structure or a stacked-layer structure of two or more insulators.

(632) Accordingly, the source region and the drain region can be formed in a self-aligned manner owing to the deposition of the insulator **274**. Thus, minute or highly integrated semiconductor devices can also be manufactured with high yield.

(633) Here, the top surfaces and the side surfaces of the conductor **260** and the insulator **250** are covered with the insulator **270** and the insulator **272**, whereby impurity elements such as nitrogen and hydrogen can be prevented from entering the conductor **260** and the insulator **250**. Thus, the impurity elements such as nitrogen and hydrogen can be prevented from entering the region **234** functioning as the channel formation region of the transistor **202** through the conductor **260** and the insulator **250**. Accordingly, the transistor **202** having favorable electrical characteristics can be provided.

(634) Note that although the region **231** is formed by the reduction in the resistance of the oxide

230 owing to the deposition of the insulator **274** in the above, this embodiment is not limited thereto. For example, each region and the like may be formed by dopant addition treatment or plasma treatment, or the combination of these treatments.

(635) For example, plasma treatment may be performed on the oxide **230** using the insulator **250**, the conductor **260**, the insulator **272**, the insulator **273**, the insulator **270**, and the insulator **271** as masks. The plasma treatment is performed in, for example, an atmosphere containing the above-described element forming an oxygen vacancy or the above-described element trapped by an oxygen vacancy. For example, the plasma treatment is performed using an argon gas and a nitrogen gas.

(636) Subsequently, heat treatment can be performed. For the heat treatment, the above-described heat treatment conditions can be used. The heat treatment allows diffusion of the added dopant into the region **231** of the oxide **230**, resulting in an increase in on-state current. Furthermore, the added dopant may be diffused into the region **232** by this heat treatment.

(637) Next, the conductive film **130A** and a conductive film **130B** are formed to cover the insulator **274** (see FIG. **46**). The conductive film **130A** and the conductive film **130B** can be deposited by a sputtering method, a CVD method, an MBE method, a PLD method, an ALD method, or the like. In this embodiment, titanium nitride is formed by a sputtering method as the conductive film **130A**, and tungsten is formed by a sputtering method as the conductive film **130B**.

(638) Next, the conductive film **130A** and the conductive film **130B** are processed by a lithography method to form the conductor **130** (the conductor **130a** and the conductor **130b**) (see FIG. **47**). For processing the conductive film **130A** and the conductive film **130B**, a method similar to that for processing the conductive film **130A** described in Embodiment 1 can be used.

(639) In this embodiment, as illustrated in FIG. **47(B)** and FIG. **47(D)**, part of the conductor **130** provided over the oxide **230** is provided to extend outward from the oxide **230**. Specifically, the conductor **130** is provided to extend beyond the oxide **230** to the E side and the F side in FIG. **47(D)**.

(640) Such a shape is preferable because the capacitor **101** can form capacitance not only between the top surface of the oxide **230** and the conductor **130** but also between the side surface of the oxide **230** and the conductor **130**. Therefore, in FIG. **47(B)**, the conductor **130** may be provided to extend beyond the oxide **230** to the B side. In contrast, when there is a limitation on the area occupied by the cell **601**, the conductor **130** is formed so as to extend beyond the oxide **230** as little as possible; thus, the cell **601** can be miniaturized, so that the semiconductor device can be highly integrated.

(641) The conductor **130** may be formed to be connected to the conductor **130** of the adjacent cell **601**.

(642) Then, the insulator **280** is deposited over the insulator **274** and the conductor **130** (see FIG. **48**). The insulator **280** can be formed using a method and a material similar to those in Embodiment 1.

(643) Then, an opening reaching the region **231** of the oxide **230**, an opening reaching the conductor **130**, an opening reaching the conductor **260**, and an opening reaching the conductor **205** are formed in the insulator **280** and the insulator **274**, in the insulator **280**, in the insulator **280**, the insulator **274**, the insulator **271**, and the insulator **270**, and in the insulator **280**, the insulator **274**, the insulator **222**, and the insulator **220**, respectively. The openings are formed by a lithography method.

(644) Note that in order that the conductor **252a** may be provided in contact with the side surface of the oxide **230**, the opening reaching the oxide **230** is formed such that the side surface of the oxide **230** is exposed in the opening.

(645) Next, a rare gas is added to the oxide **230** exposed by forming the opening. Similar to the above, for the addition of the rare gas, for example, an ion implantation method by which an ionized source gas is subjected to mass separation and then added, an ion doping method by which

an ionized source gas is added without mass separation, a plasma immersion ion implantation method, or plasma treatment can be used. By addition of a rare gas, the region **233** is provided in the region **231** of the oxide **230** (see FIG. **49**).

(646) Next, the conductor **252** (the conductor **252a**, the conductor **252b**, the conductor **252c**, and the conductor **252d**) is formed (see FIG. **50**). A conductor electrically connected to the conductor **252** may be formed, as necessary.

(647) Through the above process, the semiconductor device including the transistor **202** and the capacitor **101** can be manufactured. As illustrated in FIG. **30** to FIG. **50**, by using the method for manufacturing a semiconductor device described in this embodiment, the transistor **202** and the capacitor **101** can be manufactured.

(648) According to one embodiment of the present invention, a semiconductor device that can be miniaturized or highly integrated can be provided. Alternatively, according to one embodiment of the present invention, a semiconductor device with favorable electrical characteristics can be provided. Alternatively, according to one embodiment of the present invention, a semiconductor device with a low off-state current can be provided. Alternatively, according to one embodiment of the present invention, a transistor with a high on-state current can be provided. Alternatively, according to one embodiment of the present invention, a highly reliable semiconductor device can be provided. Alternatively, according to one embodiment of the present invention, a semiconductor device with low power consumption can be provided. Alternatively, according to one embodiment of the present invention, a semiconductor device with high productivity can be provided.

(649) The structures, methods, and the like in this embodiment described above can be combined as appropriate with the structures, methods, and the like described in the other embodiments.

Embodiment 3

(650) In this embodiment, one embodiment of a semiconductor device will be described with reference to FIG. **51** and FIG. **52**.

(651) [Memory Device **1**]

(652) A memory device illustrated in FIG. **51** includes the transistor **200**, the capacitor **100**, and the transistor **300**.

(653) The transistor **200** is a transistor whose channel is formed in a semiconductor layer including an oxide semiconductor. Since the off-state current of the transistor **200** is low, a memory device using it can retain stored contents for a long time. In other words, since refresh operation is not required or frequency of refresh operation is extremely low, the power consumption of the memory device can be sufficiently reduced.

(654) In the memory device illustrated in FIG. **51**, a wiring **3001** is electrically connected to the source of the transistor **300**, and a wiring **3002** is electrically connected to the drain of the transistor **300**. A wiring **3003** is electrically connected to one of the source and the drain of the transistor **200**, a wiring **3004** is electrically connected to the first gate of the transistor **200**, and a wiring **3006** is electrically connected to the second gate of the transistor **200**. The other of the source and the drain of the transistor **200** functions as one electrode of the capacitor **100**, and is electrically connected to the gate of the transistor **300** through an opening formed in the insulator **220**, the insulator **222**, the insulator **224**, and the oxide **230a**. A wiring **3005** is electrically connected to the other electrode of the capacitor **100**.

(655) The memory device illustrated in FIG. **51** has a feature that the potential of the gate of the transistor **300** can be retained and thus enables writing, retaining, and reading of data as follows.

(656) Writing and retaining of data are described. First, the potential of the fourth wiring **3004** is set to a potential at which the transistor **200** is brought into a conduction state, so that the transistor **200** is brought into a conduction state. Accordingly, the potential of the third wiring **3003** is supplied to a node SN where the gate of the transistor **300** and one electrode of the capacitor **100** are electrically connected to each other. That is, a predetermined charge is supplied to the gate of the transistor **300** (writing). Here, one of charges providing two different potential levels

(hereinafter referred to as a Low-level charge and a High-level charge) is supplied. After that, the potential of the fourth wiring **3004** is set to a potential at which the transistor **200** is brought into a non-conduction state so that the transistor **200** is brought into a non-conduction state; thus, the charge is retained in the node SN (retaining).

(657) In the case where the off-state current of the transistor **200** is low, the charge of the node SN is retained for a long time.

(658) Next, reading of data is described. An appropriate potential (reading potential) is supplied to the fifth wiring **3005** in a state where a predetermined potential (constant potential) is supplied to the first wiring **3001**, whereby the second wiring **3002** has a potential corresponding to the amount of charge retained in the node SN. This is because when the transistor **300** is of an n-channel type, an apparent threshold voltage $V_{\text{sub.th_H}}$ at the time when a High-level charge is supplied to the gate of the transistor **300** is lower than an apparent threshold voltage $V_{\text{sub.th_L}}$ at the time when a Low-level charge is supplied to the gate of the transistor **300**. Here, an apparent threshold voltage refers to the potential of the fifth wiring **3005** which is needed to bring the transistor **300** into a “conduction state”. Thus, the potential of the fifth wiring **3005** is set to a potential $V_{\text{sub.0}}$ which is between $V_{\text{sub.th_H}}$ and $V_{\text{sub.th_L}}$, whereby the charge supplied to the node SN can be determined. For example, in the case where a High-level charge is supplied to the node SN in writing, when the potential of the fifth wiring **3005** is $V_{\text{sub.0}} (>V_{\text{sub.th_H}})$, the transistor **300** is brought into a “conduction state”. Meanwhile, in the case where a Low-level charge is supplied to the node SN, the transistor **300** remains in a “non-conduction state” even when the potential of the fifth wiring **3005** is $V_{\text{sub.0}} (<V_{\text{sub.th_L}})$. Thus, the data retained in the node SN can be read by determining the potential of the second wiring **3002**.

(659) <Structure of Memory Device **1**>

(660) The memory device of one embodiment of the present invention includes the transistor **300**, the transistor **200**, and the capacitor **100** as illustrated in FIG. **51**. The transistor **200** is provided above the transistor **300**, and the capacitor **100** is provided in the same layer as the transistor **200**.

(661) The transistor **300** is provided on a substrate **311** and includes a conductor **316**, an insulator **315**, a semiconductor region **313** that is part of the substrate **311**, and a low-resistance region **314a** and a low-resistance region **314b** functioning as a source region and a drain region.

(662) The transistor **300** is of either a p-channel type or an n-channel type.

(663) A region of the semiconductor region **313** where a channel is formed, a region in the vicinity thereof, the low-resistance region **314a** and the low-resistance region **314b** functioning as the source region and the drain region, and the like preferably contain a semiconductor such as a silicon-based semiconductor, further preferably contain single crystal silicon. Alternatively, the regions may be formed using a material containing Ge (germanium), SiGe (silicon germanium), GaAs (gallium arsenide), GaAlAs (gallium aluminum arsenide), or the like. Silicon whose effective mass is adjusted by applying stress to the crystal lattice and thereby changing the lattice spacing may be used. Alternatively, the transistor **300** may be a HEMT (High Electron Mobility Transistor) with GaAs and GaAlAs, or the like.

(664) The low-resistance region **314a** and the low-resistance region **314b** contain an element which imparts n-type conductivity, such as arsenic or phosphorus, or an element which imparts p-type conductivity, such as boron, in addition to the semiconductor material used for the semiconductor region **313**.

(665) The insulator **315** functions as a gate insulating film of the transistor **300**.

(666) For the conductor **316** functioning as the gate electrode, a semiconductor material such as silicon containing the element which imparts n-type conductivity, such as arsenic or phosphorus, or the element which imparts p-type conductivity, such as boron, or a conductive material such as a metal material, an alloy material, or a metal oxide material can be used.

(667) Note that the work function is determined by a material of the conductor, whereby the threshold voltage can be adjusted. Specifically, it is preferable to use a material such as titanium

nitride, tantalum nitride, or the like for the conductor. Furthermore, in order to ensure both conductivity and embeddability, it is preferable to use stacked layers of metal materials such as tungsten and aluminum for the conductor, and it is particularly preferable to use tungsten in terms of heat resistance.

(668) Note that the transistor **300** illustrated in FIG. **51** is only an example and the structure is not limited thereto; a transistor appropriate for a circuit configuration or a driving method is used.

(669) An insulator **320**, an insulator **322**, an insulator **324**, and an insulator **326** are stacked sequentially and provided to cover the transistor **300**.

(670) For the insulator **320**, the insulator **322**, the insulator **324**, and the insulator **326**, for example, silicon oxide, silicon oxynitride, silicon nitride oxide, silicon nitride, aluminum oxide, aluminum oxynitride, aluminum nitride oxide, or aluminum nitride is used.

(671) The insulator **322** may function as a planarization film for eliminating a level difference caused by the transistor **300** or the like provided below the insulator **322**. For example, atop surface of the insulator **322** may be planarized by planarization treatment using a chemical mechanical polishing (CMP) method to improve planarity.

(672) For the insulator **324**, a film having a barrier property that prevents hydrogen and impurities from being diffused from the substrate **311**, the transistor **300**, or the like into the region where the transistor **200** is provided is preferably used.

(673) For the film having a barrier property against hydrogen, silicon nitride formed by a CVD method can be used, for example. Here, diffusion of hydrogen to a semiconductor element including an oxide semiconductor, such as the transistor **200**, degrades the characteristics of the semiconductor element in some cases. Therefore, a film that inhibits hydrogen diffusion is preferably provided between the transistor **200** and the transistor **300**. The film that inhibits hydrogen diffusion is specifically a film from which a small amount of hydrogen is released.

(674) The amount of released hydrogen can be measured by thermal desorption spectroscopy (TDS), for example. The amount of hydrogen released from the insulator **324** that is converted into hydrogen atoms per area of the insulator **324** is less than or equal to 10×10^{15} atoms/cm², preferably less than or equal to 5×10^{15} atoms/cm², in the TDS analysis in the range from 50° C. to 500° C., for example.

(675) Note that the insulator **326** preferably has a lower permittivity than the insulator **324**. For example, the relative permittivity of the insulator **326** is preferably lower than 4, further preferably lower than 3. The relative permittivity of the insulator **326** is, for example, preferably 0.7 or less times, further preferably 0.6 or less times the relative permittivity of the insulator **324**. In the case where a material with a low permittivity is used for an interlayer film, the parasitic capacitance generated between wirings can be reduced.

(676) A conductor **328**, a conductor **330**, and the like that are electrically connected to the capacitor **100** or the transistor **200** are embedded in the insulator **320**, the insulator **322**, the insulator **324**, and the insulator **326**. Note that the conductor **328** and the conductor **330** each function as a plug or a wiring. A plurality of conductors functioning as plugs or wirings are collectively denoted by the same reference numeral in some cases. Furthermore, in this specification and the like, a wiring and a plug electrically connected to the wiring may be a single component. That is, part of a conductor functions as a wiring in some cases, and part of the conductor functions as a plug in some cases.

(677) As a material for each of the plugs and wirings (the conductor **328**, the conductor **330**, and the like), a single layer or stacked layers of a conductive material such as a metal material, an alloy material, a metal nitride material, or a metal oxide material can be used. It is preferable to use a high-melting-point material that has both heat resistance and conductivity, such as tungsten or molybdenum, and it is preferable to use tungsten. Alternatively, a low-resistance conductive material such as aluminum or copper is preferably used. The use of a low-resistance conductive material can reduce wiring resistance.

(678) A wiring layer may be provided over the insulator **326** and the conductor **330**. For example,

in FIG. 51, an insulator 350, an insulator 352, and an insulator 354 are stacked sequentially. Furthermore, a conductor 356 is formed in the insulator 350, the insulator 352, and the insulator 354. The conductor 356 functions as a plug or a wiring. Note that the conductor 356 can be provided using a material similar to those for the conductor 328 and the conductor 330.

(679) Note that for example, as the insulator 350, an insulator having a barrier property against hydrogen is preferably used, as with the insulator 324. Furthermore, the conductor 356 preferably includes a conductor having a barrier property against hydrogen. In particular, the conductor having a barrier property against hydrogen is formed in an opening portion of the insulator 350 having a barrier property against hydrogen. With such a structure, the transistor 300 and the transistor 200 can be separated by a barrier layer, so that diffusion of hydrogen from the transistor 300 to the transistor 200 can be inhibited.

(680) Note that as the conductor having a barrier property against hydrogen, tantalum nitride is preferably used, for example. By stacking tantalum nitride and tungsten having high conductivity, diffusion of hydrogen from the transistor 300 can be inhibited while the conductivity of a wiring is kept. In that case, a tantalum nitride layer having a barrier property against hydrogen is preferably in contact with the insulator 350 having a barrier property against hydrogen.

(681) A wiring layer may be provided over the insulator 354 and the conductor 356. For example, in FIG. 51, an insulator 360, an insulator 362, and an insulator 364 are stacked sequentially. Furthermore, a conductor 366 is formed in the insulator 360, the insulator 362, and the insulator 364. The conductor 366 functions as a plug or a wiring. Note that the conductor 366 can be provided using a material similar to those for the conductor 328 and the conductor 330.

(682) Note that for example, as the insulator 360, an insulator having a barrier property against hydrogen is preferably used, as with the insulator 324. Furthermore, the conductor 366 preferably includes a conductor having a barrier property against hydrogen. In particular, the conductor having a barrier property against hydrogen is formed in an opening portion of the insulator 360 having a barrier property against hydrogen. With such a structure, the transistor 300 and the transistor 200 can be separated by a barrier layer, so that diffusion of hydrogen from the transistor 300 to the transistor 200 can be inhibited.

(683) A wiring layer may be provided over the insulator 364 and the conductor 366. For example, in FIG. 51, an insulator 370, an insulator 372, and an insulator 374 are stacked sequentially. Furthermore, a conductor 376 is formed in the insulator 370, the insulator 372, and the insulator 374. The conductor 376 functions as a plug or a wiring. Note that the conductor 376 can be provided using a material similar to those for the conductor 328 and the conductor 330.

(684) Note that for example, as the insulator 370, an insulator having a barrier property against hydrogen is preferably used, as with the insulator 324. Furthermore, the conductor 376 preferably includes a conductor having a barrier property against hydrogen. In particular, the conductor having a barrier property against hydrogen is formed in an opening portion of the insulator 370 having a barrier property against hydrogen. With such a structure, the transistor 300 and the transistor 200 can be separated by a barrier layer, so that diffusion of hydrogen from the transistor 300 to the transistor 200 can be inhibited.

(685) A wiring layer may be provided over the insulator 374 and the conductor 376. For example, in FIG. 51, an insulator 380, an insulator 382, and an insulator 384 are stacked sequentially. Furthermore, a conductor 386 is formed in the insulator 380, the insulator 382, and the insulator 384. The conductor 386 functions as a plug or a wiring. Note that the conductor 386 can be provided using a material similar to those for the conductor 328 and the conductor 330.

(686) Note that for example, as the insulator 380, an insulator having a barrier property against hydrogen is preferably used, as with the insulator 324. Furthermore, the conductor 386 preferably includes a conductor having a barrier property against hydrogen. In particular, the conductor having a barrier property against hydrogen is formed in an opening portion of the insulator 380 having a barrier property against hydrogen. With such a structure, the transistor 300 and the transistor 200

can be separated by a barrier layer, so that diffusion of hydrogen from the transistor **300** to the transistor **200** can be inhibited.

(687) The insulator **210** is provided over the insulator **384** and the conductor **386**. A substance having a barrier property against oxygen and hydrogen is preferably used for the insulator **210**.

(688) The conductor **203**, the conductor **205**, and the insulator **216** are provided over the insulator **210**.

(689) For the insulator **210**, for example, a film having a barrier property that prevents hydrogen and impurities from being diffused from the substrate **311** or a region where the transistor **300** is provided into the region where the transistor **200** is provided. Therefore, a material similar to that for the insulator **324** can be used.

(690) For the film having a barrier property against hydrogen, silicon nitride formed by a CVD method can be used. Here, diffusion of hydrogen to a semiconductor element including an oxide semiconductor, such as the transistor **200**, degrades the characteristics of the semiconductor element in some cases. Therefore, a film that inhibits hydrogen diffusion is preferably provided between the transistor **200** and the transistor **300**. The film that inhibits hydrogen diffusion is specifically a film from which a small amount of hydrogen is released.

(691) For the film having a barrier property against hydrogen used for the insulator **210**, for example, a metal oxide such as aluminum oxide, hafnium oxide, or tantalum oxide is preferably used.

(692) In particular, aluminum oxide has an excellent blocking effect that prevents passage of oxygen and impurities such as hydrogen and moisture which cause a change in electrical characteristics of the transistor. Accordingly, aluminum oxide can prevent entry of impurities such as hydrogen and moisture into the transistor **200** during a manufacturing process of the transistor and after the manufacturing. In addition, release of oxygen from the oxide included in the transistor **200** can be inhibited. Therefore, aluminum oxide is suitably used for a protective film of the transistor **200**.

(693) The transistor **200** and the capacitor **100** are provided over the insulator **210**. Note that the structures of the transistor **200** and the capacitor **100** described in the above embodiments can be used as those of the transistor **200** and the capacitor **100**. The transistor **200** illustrated in FIG. **51** is an example and the structure is not limited thereto; a transistor appropriate for a circuit configuration or a driving method is used.

(694) FIG. **52** illustrates an example in which the capacitor **100** is provided over the transistor **200**. The conductor **256** electrically connected to the other of the source and the drain of the transistor **200** is used as one electrode of the capacitor **100**. The conductor **256** is electrically connected to the gate of the transistor **300**. An insulator **120** functioning as a dielectric of the capacitor **100** is provided over the conductor **256**. A conductor **131** is provided to overlap with the conductor **256** with the insulator **120** interposed therebetween. The conductor **131** functions as the other electrode of the capacitor **100** and is electrically connected to the wiring **3005**.

(695) The insulator **120** may be provided to cover a side surface of the conductor **256**. The conductor **131** may be provided on the side surface of the conductor **256** with the insulator **120** therebetween. Such a structure is preferable because the capacitor **100** can be formed of not only the top surface of the conductor **256** and the conductor **131** facing the top surface of the conductor **256** but also the side surface of the conductor **256** and the conductor **131** facing the side surface of the conductor **256** and thus the capacitance value can be increased without increasing the area of a top surface of the capacitor **100**.

(696) The above is the description of the structure example. With the use of this structure, a semiconductor device using a transistor including an oxide semiconductor can have a suppressed variation in electrical characteristics and improved reliability. Alternatively, a transistor including an oxide semiconductor with a high on-state current can be provided. Alternatively, a transistor including an oxide semiconductor with a low off-state current can be provided. Alternatively, a

semiconductor device with low power consumption can be provided.

(697) The structures, methods, and the like in this embodiment described above can be combined as appropriate with the structures, methods, and the like described in the other embodiments.

Embodiment 4

(698) In this embodiment, one embodiment of a semiconductor device will be described with reference to FIG. 53 to FIG. 56.

(699) In the semiconductor device of this embodiment, materials similar to those in Embodiment 1 to Embodiment 3 can be used for components with the same reference numerals as the semiconductor device in Embodiment 1 to Embodiment 3. Unless otherwise specified, the components formed in this embodiment can obtain structural characteristics and effects similar to those of the components described in Embodiment 1 to Embodiment 3, and description thereof is omitted.

(700) [Memory Device 2]

(701) Memory devices illustrated in FIG. 53(A) and FIG. 54 each include the transistor 202, the capacitor 101, and the transistor 300, which are described in Embodiment 2.

(702) <Structure of Memory Device 2>

(703) The memory device illustrated in FIG. 53(A) includes the transistor 300; the insulator 350, the insulator 352, and the insulator 354 over the transistor 300 which are provided with the conductor 356; the insulator 210 over the insulator 354 and the conductor 356; and the transistor 202 and the capacitor 101 over the insulator 210.

(704) The memory device illustrated in FIG. 54 includes the transistor 300; the insulator 350, the insulator 352, and the insulator 354 over the transistor 300 which are provided with the conductor 356; the insulator 360, the insulator 362, and the insulator 364 which are provided with the conductor 366; the insulator 370, the insulator 372, and the insulator 374 which are provided with the conductor 376; the insulator 380, the insulator 382, and the insulator 384 which are provided with the conductor 386; the insulator 210 over the insulator 384 and the conductor 386; and the transistor 202 and the capacitor 101 over the insulator 210.

(705) The transistor 202 and the capacitor 101 illustrated in FIG. 53(A) and FIG. 54 have some components in common and thus have a small projected area, which enables miniaturization and high integration.

(706) Writing, retaining, and reading of data in the memory devices illustrated in FIG. 53(A) and FIG. 54 are performed as in methods similar to those described in Embodiment 3, and description thereof is omitted.

(707) Note that the transistor 300 illustrated in FIG. 53(A) and FIG. 54 is only an example and the structure is not limited thereto; a transistor appropriate for a circuit configuration or a driving method is used.

(708) Here, FIG. 53(B) shows a cross-sectional view of the transistor 300 in the W width direction denoted by W1-W2 in FIG. 53(A) and FIG. 54. In the transistor 300, the semiconductor region 313 (part of the substrate 311) where a channel is formed has a convex shape as illustrated in FIG. 53(B). The conductor 316 is provided to cover side surfaces and atop surface of the semiconductor region 313 with the insulator 315 therebetween. Note that for the conductor 316, a material that adjusts the work function may be used. Such a transistor 300 is also referred to as a FIN-type transistor because it utilizes a convex portion of the semiconductor substrate. Note that an insulator functioning as a mask for forming the convex portion may be included in contact with an upper portion of the convex portion. Furthermore, although the case where the convex portion is formed by processing part of the semiconductor substrate is described here, a semiconductor film having a convex shape may be formed by processing an SOI substrate.

(709) For the insulator 324, a film having a barrier property that prevents hydrogen and impurities from being diffused from the substrate 311, the transistor 300, or the like into the region where the transistor 202 is provided is preferably used.

(710) The insulator **210**, the insulator **212**, and the insulator **216** are stacked sequentially and provided over the insulator **354** and the conductor **356**. A substance having a barrier property against oxygen and hydrogen is preferably used for one of the insulator **210**, the insulator **212**, and the insulator **216**.

(711) For the insulator **210**, the insulator **212**, and the insulator **216**, for example, a film having a barrier property that prevents hydrogen and impurities from being diffused from the substrate **311** or a region where the transistor **300** is provided into the region where the transistor **202** is provided. Therefore, a material similar to that for the insulator **324** can be used.

(712) For the film having a barrier property against hydrogen used for the insulator **210**, the insulator **212**, and the insulator **216**, for example, a metal oxide such as aluminum oxide, hafnium oxide, or tantalum oxide is preferably used.

(713) For the insulator **212** and the insulator **216**, for example, an interlayer film of a material with a relatively low permittivity is used, whereby the parasitic capacitance generated between wirings can be reduced. A silicon oxide film or a silicon oxynitride film can be used for the insulator **212** and the insulator **216**, for example.

(714) The conductor **209**, the conductor **203**, the conductor **205**, and the like, which are conductors included in the transistor **202**, are embedded in the insulator **210**, the insulator **212**, and the insulator **216**. Note that the conductor **203** and the conductor **209** each function as a plug or a wiring that electrically connects the transistor **202** and the transistor **300**. The conductor **209**, the conductor **203**, and the conductor **205** can be provided using a material similar to those for the conductor **328** and the conductor **330**.

(715) In particular, the conductor **209** in a region in contact with the insulator **210** and the insulator **212** is preferably a conductor having a barrier property against oxygen, hydrogen, and water. With such a structure, the transistor **300** and the transistor **202** can be separated by a layer having a barrier property against oxygen, hydrogen, and water, whereby diffusion of hydrogen from the transistor **300** to the transistor **202** can be inhibited.

(716) The transistor **202** and the capacitor **101** are provided over the insulator **212**. Note that the structures of the transistor **202** and the capacitor **101** described in the above embodiments can be used as those of the transistor **202** and the capacitor **101**. The transistor **202** and the capacitor **101** illustrated in FIG. 53(A) are examples and the structures are not limited thereto; a transistor appropriate for a circuit configuration or a driving method is used.

(717) Here, FIG. 54 illustrates an example in which the gate of the transistor **300** and the other of the source and the drain of the transistor **202** are electrically connected to each other through the four conductors: the conductor **356**, the conductor **366**, the conductor **376**, and the conductor **386**; however, this embodiment is not limited thereto. A conductor provided between the gate of the transistor **300** and the other of the source and the drain of the transistor **202** may be only the conductor **356**, or two, three, or five or more conductors may be provided. Alternatively, the conductor **330** electrically connected to the gate of the transistor **300** and the conductor **209** electrically connected to the other of the source and the drain of the transistor **202** may be directly connected to each other.

(718) The above is the description of the structure example. With the use of this structure, a semiconductor device using a transistor including an oxide semiconductor can have a suppressed variation in electrical characteristics and improved reliability. Alternatively, a transistor including an oxide semiconductor with a high on-state current can be provided. Alternatively, a transistor including an oxide semiconductor with a low off-state current can be provided. Alternatively, a semiconductor device with low power consumption can be provided.

(719) <Modification Example of Memory Device 2>

(720) FIG. 55 and FIG. 56 show a modification example of this embodiment.

(721) When memory devices illustrated in FIG. 55 are integrated as memory cells, a memory cell array can be formed. For example, in a circuit diagram shown in FIG. 56, a plurality of memory

devices are provided so that memory cells are arranged in a matrix. FIG. 55 is an example of a cross-sectional view of a memory cell array in the case where the transistors **202** are integrated in the memory device illustrated in FIG. 53.

(722) FIG. 55 and FIG. 56 illustrate a memory cell array including a memory device including the transistor **300a**, the transistor **202a**, and the capacitor **101a**, a memory device including the transistor **300b**, the transistor **202b**, and the capacitor **101b**, the wiring SL, wirings RBL (RBL**01** and RBL**02**), wirings WBL (WBL**01** and WBL**02**), a wiring WWL, and a wiring RWL.

(723) For example, as illustrated in FIG. 55, the transistor **202a** and the transistor **202b** can be provided to overlap with each other. The wiring SL can be provided in common with the transistor **300a** and the transistor **300b**. For example, when the low-resistance region **314a** is provided as the wiring SL in common with the transistor **300a** and the transistor **300b**, formation of a wiring or a plug is unnecessary; thus, the process can be shortened. This structure can also lead to a reduction in area, higher integration, and miniaturization of the semiconductor device.

(724) The structures, methods, and the like in this embodiment described above can be combined as appropriate with the structures, methods, and the like described in the other embodiments.

Embodiment 5

(725) In this embodiment, a NOSRAM will be described as an example of a memory device, which is one embodiment of the present invention, including a transistor in which an oxide is used for a semiconductor (hereinafter referred to as an OS transistor) and a capacitor with reference to FIG. 57 to FIG. 60. A NOSRAM (registered trademark) is an abbreviation of “Nonvolatile Oxide Semiconductor RAM”, which indicates a RAM including a gain cell (2T or 3T) memory cell. Note that hereinafter, a memory device including an OS transistor, such as a NOSRAM, is referred to as an OS memory in some cases.

(726) A memory device in which OS transistors are used in memory cells (hereinafter referred to as an “OS memory”) is used in a NOSRAM. The OS memory is a memory including at least a capacitor and an OS transistor that controls charge and discharge of the capacitor. The OS memory has excellent retention characteristics because the OS transistor has an extremely low off-state current and thus can function as a nonvolatile memory.

(727) <<NOSRAM>>

(728) FIG. 57 illustrates a configuration example of a NOSRAM. A NOSRAM **1600** illustrated in FIG. 57 includes a memory cell array **1610**, a controller **1640**, a row driver **1650**, a column driver **1660**, and an output driver **1670**. Note that the NOSRAM **1600** is a multilevel NOSRAM in which one memory cell stores multilevel data.

(729) The memory cell array **1610** includes a plurality of memory cells **1611**, a plurality of word lines WWL and RWL, bit lines BL, and source lines SL. The word lines WWL are write word lines and the word lines RWL are read word lines. In the NOSRAM **1600**, one memory cell **1611** stores 3-bit (8-level) data.

(730) The controller **1640** controls the NOSRAM **1600** as a whole and writes data WDA[31:0] and reads out data RDA[31:0]. The controller **1640** processes command signals from the outside (for example, a chip enable signal and a write enable signal) to generate control signals of the row driver **1650**, the column driver **1660**, and the output driver **1670**.

(731) The row driver **1650** has a function of selecting a row to be accessed. The row driver **1650** includes a row decoder **1651** and a word line driver **1652**.

(732) The column driver **1660** drives the source lines SL and the bit lines BL. The column driver **1660** includes a column decoder **1661**, a write driver **1662**, and a DAC (digital-analog converter circuit) **1663**.

(733) The DAC **1663** converts 3-bit digital data into an analog voltage. The DAC **1663** converts 32-bit data WDA[31:0] into an analog voltage per 3 bits.

(734) The write driver **1662** has a function of precharging the source lines SL, a function of bringing the source lines SL into an electrically floating state, a function of selecting a source line

SL, a function of inputting a writing voltage generated in the DAC **1663** to the selected source line SL, a function of precharging the bit lines BL, a function of bringing the bit lines BL into an electrically floating state, and the like.

(735) The output driver **1670** includes a selector **1671**, an ADC (analog-digital converter circuit) **1672**, and an output buffer **1673**. The selector **1671** selects a source line SL to be accessed and transmits the voltage of the selected source line SL to the ADC **1672**. The ADC **1672** has a function of converting an analog voltage into 3-bit digital data. The voltage of the source line SL is converted into 3-bit data in the ADC **1672**, and the output buffer **1673** retains the data output from the ADC **1672**.

(736) Note that the configuration of the row driver **1650**, the column driver **1660**, and the output driver **1670** described in this embodiment is not limited to the above. The arrangement of the drivers and wirings connected to the drivers may be changed or the functions of the drivers and the wirings connected to the drivers may be changed or added, depending on the configuration, the driving method, or the like of the memory cell array **1610**. For example, the bit lines BL may have part of a function of the source lines SL.

(737) Note that although the amount of data retained in each of the memory cells **1611** is 3 bits in the above description, the structure of the memory device described in this embodiment is not limited thereto. The amount of data retained in each of the memory cells **1611** may be 2 bits or less or 4 bits or more. In the case where the amount of data retained in each of the memory cells **1611** is one bit, for example, the DAC **1663** and the ADC **1672** is not necessarily provided.

(738) <Memory Cell>

(739) FIG. **58(A)** is a circuit diagram showing a configuration example of the memory cell **1611**. The memory cell **1611** is a 2T gain cell and the memory cell **1611** is electrically connected to the word lines WWL and RWL, the bit line BL, the source line SL, and a wiring BGL. The memory cell **1611** includes a node SN, an OS transistor MO**61**, a transistor MP**61**, and a capacitor C**61**. The OS transistor MO**61** is a write transistor. The transistor MP**61** is a read transistor and is formed using a p-channel Si transistor, for example. The capacitor C**61** is a storage capacitor for retaining the voltage of the node SN. The node SN is a node for data retaining and corresponds to a gate of the transistor MP**61** here.

(740) The write transistor of the memory cell **1611** is formed using the OS transistor MO**61**; thus, the NOSRAM **1600** can retain data for a long time.

(741) In the example of FIG. **58(A)**, write and read bit lines are a common bit line; however, as illustrated in FIG. **58(B)**, a bit line WBL functioning as a write bit line and a bit line RBL functioning as a read bit line may be provided.

(742) FIG. **58(C)** to FIG. **58(E)** show other configuration examples of the memory cell. FIG. **58(C)** to FIG. **58(E)** show examples where the write bit line WBL and the read bit line RBL are provided; however, as in FIG. **58(A)**, a bit line shared in writing and reading may be provided.

(743) A memory cell **1612** illustrated in FIG. **58(C)** is a modification example of the memory cell **1611** where the read transistor is changed into an n-channel transistor (MN**61**). The transistor MN**61** may be an OS transistor or a Si transistor.

(744) In the memory cells **1611** and **1612**, the OS transistor MO**61** may be an OS transistor with no back gate.

(745) A memory cell **1613** illustrated in FIG. **58(D)** is a 3T gain cell and is electrically connected to the word lines WWL and RWL, the bit lines WBL and RBL, the source line SL, the wirings BGL, and wirings PCL. The memory cell **1613** includes the node SN, an OS transistor MO**62**, a transistor MP**62**, a transistor MP**63**, and a capacitor C**62**. The OS transistor MO**62** is a write transistor. The transistor MP**62** is a read transistor and the transistor MP**63** is a selection transistor.

(746) A memory cell **1614** illustrated in FIG. **58(E)** is a modification example of the memory cell **1613** where the read transistor and the selection transistor are changed into n-channel transistors (MN**62** and MN**63**). The transistors MN**62** and MN**63** may be OS transistors or Si transistors.

(747) The OS transistors provided in the memory cell **1611** to the memory cell **1614** may each be a transistor with no back gate or a transistor with a back gate.

(748) A so-called NOR memory device in which the memory cells **1611** or the like are connected in parallel is described above, but the memory device of this embodiment is not limited thereto.

(749) For example, a so-called NAND memory device in which memory cells **1615** described below are connected in series may be provided.

(750) FIG. **59** is a circuit diagram showing a configuration example of the NAND memory cell array **1610**. The memory cell array **1610** illustrated in FIG. **59** includes the source line SL, the bit line RBL, the bit line WBL, the word line WWL, the word line RWL, the wiring BGL, and the memory cell **1615**. The memory cell **1615** includes the node SN, an OS transistor **MO63**, a transistor **MN64**, and a capacitor **C63**. Here, the transistor **MN64** is an n-channel Si transistor, for example. The transistor **MN64** is not limited thereto and may be a p-channel Si transistor or an OS transistor.

(751) A memory cell **1615a** and a memory cell **1615b**, which are illustrated in FIG. **59**, are described below as examples. Here, the character “a” or “b” is added to the reference numerals of the wirings and circuit elements connected to the memory cell **1615a** or the memory cell **1615b**.

(752) In the memory cell **1615a**, a gate of a transistor **MN64a**, one of a source and a drain of a transistor **MO63a**, and one electrode of a capacitor **C63a** are electrically connected to each other. The bit line WBL and the other of the source and the drain of the transistor **MO63a** are electrically connected to each other. A word line WWLa and a gate of the transistor **MO63a** are electrically connected to each other. A wiring BGLa and a back gate of the transistor **MO63a** are electrically connected to each other. A word line RWLa and the other electrode of the capacitor **C63a** are electrically connected to each other.

(753) The memory cell **1615b** can be provided to be symmetric to the memory cell **1615a** with the use of a contact portion to the bit line WBL as a symmetry axis. Therefore, circuit elements of the memory cell **1615b** are connected to wirings in a manner similar to that for the memory cell **1615a**.

(754) A source of the transistor **MN64a** of the memory cell **1615a** is electrically connected to a drain of a transistor **MN64b** of the memory cell **1615b**. A drain of the transistor **MN64a** of the memory cell **1615a** is electrically connected to the bit line RBL. A source of the transistor **MN64b** of the memory cell **1615b** is electrically connected to the source line SL through the transistors **MN64** of the plurality of memory cells **1615**. As described here, the plurality of transistors **MN64** are connected in series between the bit line RBL and the source line SL in the NAND memory cell array **1610**.

(755) Here, FIG. **60** shows a cross-sectional view corresponding to the memory cell **1615a** and the memory cell **1615b**. The memory cell **1615a** and the memory cell **1615b** have a structure similar to that of the memory device illustrated in FIG. **29**. That is, the capacitor **C63a** and a capacitor **C63b** have a structure similar to that of the capacitor **100**, the OS transistor **MO63a** and an OS transistor **MO63b** have a structure similar to that of the transistor **200**, and the transistor **MN64a** and the transistor **MN64b** have a structure similar to that of the transistor **300**. Note that for the components illustrated in FIG. **60**, which are given the same reference numerals as the components illustrated in FIG. **29**, the description thereof can be referred to.

(756) In the memory cell **1615a**, the conductor **130b** is provided to extend and functions as the word line RWLa, the conductor **260** is provided to extend and functions as the word line WWLa, and the conductor **209** in contact with a bottom surface of the conductor **205** is provided to extend and functions as the wiring BGLa. In the memory cell **1615b**, a word line RWLb, a word line WWLb, and a wiring BGLb are provided in a manner similar to the above-described manner.

(757) The low-resistance region **314b** illustrated in FIG. **60** functions as the source of the transistor **MN64a** and the drain of the transistor **MN64b**. The low-resistance region **314a** functioning as the drain of the transistor **MN64a** is electrically connected to the bit line RBL through the conductor **328** and the conductor **330**. The source of the transistor **MN64b** is electrically connected to the

source line SL through the transistors MN64 of the plurality of memory cells 1615, the conductor 328, and the conductor 330.

(758) The conductor 256 is provided to extend and functions as the bit line WBL. Here, the conductor 252a functions as a contact portion to the word line WBL and is used in common with the transistor MO63a and the transistor MO63b. Since the contact portion to the bit line WBL is shared by the memory cell 1615a and the memory cell 1615b, the number of contact portions to the bit line WBL can be reduced and the area occupied by the memory cell 1615 when seen from the above can be reduced. Accordingly, the memory device of this embodiment can be further highly integrated and the storage capacity per unit area can be increased.

(759) In a memory device including the memory cell array 1610 illustrated in FIG. 59, writing operation and reading operation are performed for every plurality of memory cells (hereinafter referred to as a memory cell column) connected to the same word line WWL (or the word line RWL). For example, the writing operation can be performed as follows. A potential at which the transistor MO63 is turned on is supplied to the word line WWL connected to a memory cell column on which writing is to be performed so that the transistors MO63 in the memory cell column on which writing is to be performed are turned on. Accordingly, the potential of the bit line WBL is supplied to the gates of the transistors MN64 and one electrode of the capacitors C63 in the selected memory cell column, whereby a predetermined charge is supplied to the gates. Thus, data can be written to the memory cells 1615 in the selected memory cell column.

(760) For example, the reading operation can be performed as follows. First, a potential at which the transistor MN64 is turned on is supplied to the word lines RWL not connected to a memory cell column on which reading is to be performed regardless of a charge supplied to the gates of the transistors MN64, so that the transistors MN64 in memory cell columns other than the memory cell column on which reading is to be performed are turned on. Then, a potential (reading potential) at which an on state or an off state of the transistor MN64 is selected is supplied to the word line RWL connected to the memory cell column on which reading is to be performed in accordance with a charge of the gates of the transistors MN64. After that, a constant potential is supplied to the source line SL and a reading circuit connected to the bit line RBL is operated. Here, the plurality of transistors MN64 between the source line SL and the bit line RBL are turned on except the transistor MN64 in the memory cell column on which reading is to be performed; therefore, the conductance between the source line SL and the bit line RBL depends on the state (an on state or an off state) of the transistor MN64 in the memory cell column on which reading is to be performed. Since the conductance of the transistor varies depending on the charge of the gate of the transistor MN64 in the memory cell column on which reading is to be performed, the potential of the bit line RBL varies accordingly. By reading the potential of the bit line RBL with the reading circuit, data can be read from the memory cell 1615 in the selected memory cell column.

(761) There is theoretically no limitation on the number of rewriting operations of the NOSRAM 1600 because data is rewritten by charging and discharging the capacitor C61, the capacitor C62, or the capacitor C63; and writing and reading of data can be performed with low energy. Furthermore, since data can be retained for a long time, the refresh rate can be reduced.

(762) In the case where the semiconductor device described in any of the above embodiments is used for the memory cells 1611, 1612, 1613, 1614, and 1615, the transistors 200 can be used as the OS transistors MO61, MO62, and MO63, the capacitors 100 can be used as the capacitors C61, C62, and C63, and the transistors 300 can be used as the transistors MP61, MP62, MP63, MN61, MN62, MN63, and MN64. Thus, the area occupied by one set consisting of a transistor and a capacitor can be reduced when seen from the above, so that the memory device of this embodiment can be further highly integrated. As a result, storage capacity per unit area of the memory device of this embodiment can be increased.

(763) The structure described in this embodiment can be used in appropriate combination with the structure described in the other embodiments.

Embodiment 6

(764) In this embodiment, a DOSRAM is described as an example of the memory device of one embodiment of the present invention, which includes an OS transistor and a capacitor, with reference to FIG. 61 and FIG. 62. A DOSRAM (registered trademark) is an abbreviation of “Dynamic Oxide Semiconductor RAM”, which is a RAM including a 1T (transistor) 1C (capacitor) memory cell. As in the NOSRAM, an OS memory is used in the DOSRAM.

(765) <<DOSRAM 1400>>

(766) FIG. 61 illustrates a configuration example of a DOSRAM. As illustrated in FIG. 61, a DOSRAM 1400 includes a controller 1405, a row circuit 1410, a column circuit 1415, and a memory cell and sense amplifier array 1420 (hereinafter referred to as an “MC-SA array 1420”).

(767) The row circuit 1410 includes a decoder 1411, a word line driver circuit 1412, a column selector 1413, and a sense amplifier driver circuit 1414. The column circuit 1415 includes a global sense amplifier array 1416 and an input/output circuit 1417. The global sense amplifier array 1416 includes a plurality of global sense amplifiers 1447. The MC-SA array 1420 includes a memory cell array 1422, a sense amplifier array 1423, and global bit lines GBLL and GBLR.

(768) (MC-SA array 1420)

(769) The MC-SA array 1420 has a stacked-layer structure in which the memory cell array 1422 is stacked over the sense amplifier array 1423. The global bit lines GBLL and GBLR are stacked over the memory cell array 1422. The DOSRAM 1400 adopts, as the bit-line structure, a hierarchical bit line structure hierarchized with local bit lines and global bit lines.

(770) The memory cell array 1422 includes N local memory cell arrays 1425<0> to 1425<N-1> (N is an integer greater than or equal to 2). FIG. 62(A) illustrates a configuration example of the local memory cell array 1425. The local memory cell array 1425 includes a plurality of memory cells 1445, a plurality of word lines WL, and a plurality of bit lines BLL and BLR. In the example of FIG. 62(A), the local memory cell array 1425 has an open bit-line architecture but may have a folded bit-line architecture.

(771) FIG. 62(B) illustrates a circuit configuration example of the memory cell 1445. The memory cell 1445 includes a transistor MW1, a capacitor CS1, and terminals B1 and B2. The transistor MW1 has a function of controlling charging and discharging of the capacitor CS1. A gate of the transistor MW1 is electrically connected to the word line WL, a first terminal of the transistor MW1 is electrically connected to the bit line (BLL or BLR), and a second terminal of the transistor MW1 is electrically connected to a first terminal of the capacitor CS1. A second terminal of the capacitor CS1 is electrically connected to the terminal B2. A constant voltage (for example, a low power supply voltage) is input to the terminal B2.

(772) In the case where the semiconductor device described in any of the above embodiments is used in the memory cell 1445, the transistor 200 can be used as the transistor MW1, and the capacitor 100 can be used as the capacitor CS1. In this case, the area occupied by one set consisting of a transistor and a capacitor can be reduced when seen from the above; accordingly, the memory device of this embodiment can be highly integrated. As a result, storage capacity per unit area of the memory device of this embodiment can be increased.

(773) The transistor MW1 includes a back gate, and the back gate is electrically connected to the terminal BT. This makes it possible to change the threshold voltage of the transistor MW1 with a voltage of the terminal B1. For example, the voltage of the terminal B1 may be a fixed voltage (for example, a negative constant voltage), or the voltage of the terminal B1 may be changed in response to the operation of the DOSRAM 1400.

(774) The back gate of the transistor MW1 may be electrically connected to the gate, the first terminal, or the second terminal of the transistor MW1. Alternatively, the back gate is not necessarily provided in the transistor MW1.

(775) The sense amplifier array 1423 includes N local sense amplifier arrays 1426<0> to 1426<N-1>. The local sense amplifier array 1426 includes one switch array 1444 and a plurality of

sense amplifiers **1446**. A bit line pair is electrically connected to the sense amplifier **1446**. The sense amplifier **1446** has a function of precharging the bit line pair, a function of amplifying a voltage difference between the bit line pair, and a function of retaining the voltage difference. The switch array **1444** has a function of selecting a bit line pair and bringing the selected bit line pair and a global bit line pair into a conduction state.

(776) Here, the bit line pair refers to two bit lines which are compared by the sense amplifier at the same time. The global bit line pair refers to two global bit lines which are compared by the global sense amplifier at the same time. The bit line pair can be referred to as a pair of bit lines, and the global bit line pair can be referred to as a pair of global bit lines. Here, the bit line BLL and the bit line BLR form one bit line pair. The global bit line GBLL and the global bit line GBLR form one global bit line pair. In the following description, the expressions “bit line pair (BLL, BLR)” and “global bit line pair (GBLL, GBLR)” are also used.

(777) (Controller **1405**)

(778) The controller **1405** has a function of controlling the overall operation of the DOSRAM **1400**. The controller **1405** has a function of performing logic operation on a command signal input from the outside and determining an operation mode, a function of generating control signals for the row circuit **1410** and the column circuit **1415** so that the determined operation mode is executed, a function of retaining an address signal input from the outside, and a function of generating an internal address signal.

(779) (Row Circuit **1410**)

(780) The row circuit **1410** has a function of driving the MC-SA array **1420**. The decoder **1411** has a function of decoding an address signal. The word line driver circuit **1412** generates a selection signal for selecting a word line WL of a target row to be accessed.

(781) The column selector **1413** and the sense amplifier driver circuit **1414** are circuits for driving the sense amplifier array **1423**. The column selector **1413** has a function of generating a selection signal for selecting a bit line of a target column to be accessed. With the selection signal from the column selector **1413**, the switch array **1444** of each local sense amplifier array **1426** is controlled. With the control signal from the sense amplifier driver circuit **1414**, the plurality of local sense amplifier arrays **1426** are independently driven.

(782) (Column Circuit **1415**)

(783) The column circuit **1415** has a function of controlling the input of data signals WDA[31:0], and a function of controlling the output of data signals RDA[31:0]. The data signals WDA[31:0] are write data signals, and the data signals RDA[31:0] are read data signals.

(784) The global sense amplifier **1447** is electrically connected to the global bit line pair (GBLL, GBLR). The global sense amplifier **1447** has a function of amplifying a voltage difference between the global bit line pair (GBLL, GBLR), and a function of retaining the voltage difference. Data is written to and read from the global bit line pair (GBLL, GBLR) by the input/output circuit **1417**.

(785) The writing operation of the DOSRAM **1400** is briefly described. Data is written to the global bit line pair by the input/output circuit **1417**. The data of the global bit line pair is retained by the global sense amplifier array **1416**. By the switch array **1444** of the local sense amplifier array **1426** specified by an address signal, the data of the global bit line pair is written to the bit line pair of a target column. The local sense amplifier array **1426** amplifies and retains the written data. In the specified local memory cell array **1425**, the word line WL of a target row is selected by the row circuit **1410**, and the data retained at the local sense amplifier array **1426** is written to the memory cell **1445** of the selected row.

(786) The reading operation of the DOSRAM **1400** is briefly described. One row of the local memory cell array **1425** is specified by an address signal. In the specified local memory cell array **1425**, the word line WL of a target row is in a selected state, and data of the memory cell **1445** is written to the bit line. The local sense amplifier array **1426** detects and retains a voltage difference between the bit line pair of each column as data. Among the data retained at the local sense

amplifier array **1426**, the data of a column specified by the address signal is written to the global bit line pair by the switch array **1444**. The global sense amplifier array **1416** detects and retains the data of the global bit line pair. The data retained at the global sense amplifier array **1416** is output to the input/output circuit **1417**. Thus, the reading operation is completed.

(787) There is theoretically no limitation on the number of rewriting operations of the DOSRAM **1400** because data is rewritten by charging and discharging of the capacitor CS1; and data can be written and read with low energy. In addition, the memory cell **1445** has a simple circuit configuration, and thus the capacity can be easily increased.

(788) The transistor MW1 is an OS transistor. The extremely low off-state current of the OS transistor can inhibit charge leakage from the capacitor CS1. Therefore, the retention time of the DOSRAM **1400** is much longer than that of a DRAM. This allows less frequent refresh, which can reduce power needed for refresh operations. Thus, the DOSRAM **1400** is suitable for a memory device that rewrites a large volume of data with a high frequency, for example, a frame memory used for image processing.

(789) Since the MC-SA array **1420** has a stacked-layer structure, the bit line can be shortened to a length that is close to the length of the local sense amplifier array **1426**. A shorter bit line results in smaller bit line capacitance, which can reduce the storage capacitance of the memory cell **1445**. In addition, providing the switch array **1444** in the local sense amplifier array **1426** can reduce the number of long bit lines. For the reasons described above, a driving load during access to the DOSRAM **1400** is reduced, enabling a reduction in power consumption.

(790) The structure described in this embodiment can be used in appropriate combination with the structure described in the other embodiments.

Embodiment 7

(791) In this embodiment, an FPGA (field-programmable gate array) is described as an example of a semiconductor device of one embodiment of the present invention in which an OS transistor and a capacitor are used, with reference to FIG. **63** to FIG. **66**. In the FPGA of this embodiment, an OS memory is used for a configuration memory and a register. Here, such an FPGA is referred to as an “OS-FPGA”.

(792) <<OS-FPGA>>

(793) FIG. **63(A)** illustrates a configuration example of an OS-FPGA. An OS-FPGA **3110** illustrated in FIG. **63(A)** is capable of NOFF (normally-off) computing that executes context switching by a multi-context configuration and fine-grained power gating in each PLE. The OS-FPGA **3110** includes a controller **3111**, a word driver **3112**, a data driver **3113**, and a programmable area **3115**.

(794) The programmable area **3115** includes two input/output blocks (IOBs) **3117** and a core **3119**. The IOB **3117** includes a plurality of programmable input/output circuits. The core **3119** includes a plurality of logic array blocks (LABs) **3120** and a plurality of switch array blocks (SABs) **3130**. The LAB **3120** includes a plurality of PLEs **3121**. FIG. **63(B)** illustrates an example in which the LAB **3120** includes five PLEs **3121**. As illustrated in FIG. **63(C)**, the SAB **3130** includes a plurality of switch blocks (SBs) **3131** arranged in an array. The LAB **3120** is connected to the LABs **3120** in four directions (on the left, right, top, and bottom sides) through its input terminals and the SABs **3130**.

(795) The SB **3131** is described with reference to FIG. **64(A)** to FIG. **64(C)**. To the SB **3131** illustrated in FIG. **64(A)**, data, datab, and signals context[1:0] and word[1:0] are input. The data and the datab are configuration data, and the logics of the data and the datab have a complementary relationship. The number of contexts in the OS-FPGA **3110** is two, and the signals context[1:0] are context selection signals. The signals word[1:0] are word line selection signals, and wirings to which the signals word[1:0] are input are each a word line.

(796) The SB **3131** includes PRSs (programmable routing switches) **3133[0]** and **3133[1]**. The PRSs **3133[0]** and **3133[1]** each include a configuration memory (CM) that can store

complementary data. Note that in the case where the PRS 3133[0] and the PRS 3133[1] are not distinguished from each other, they are each referred to as a PRS 3133. The same applies to other elements.

(797) FIG. 64(B) illustrates a circuit configuration example of the PRS 3133[0]. The PRS 3133[0] and the PRS 3133[1] have the same circuit configuration. The PRS 3133[0] and the PRS 3133[1] are different from each other in a context selection signal and a word line selection signal that are input. The signals context[0] and word[0] are input to the PRS 3133[0], and the signals context[1] and word[1] are input to the PRS 3133[1]. For example, in the SB 3131, when the signal context[0] is set to “H”, the PRS 3133[0] is activated.

(798) The PRS 3133[0] includes a CM 3135 and a Si transistor M31. The Si transistor M31 is a pass transistor that is controlled by the CM 3135. The CM 3135 includes memory circuits 3137 and 3137B. The memory circuits 3137 and 3137B have the same circuit configuration. The memory circuit 3137 includes a capacitor C31 and OS transistors MO31 and MO32. The memory circuit 3137B includes a capacitor CB31 and OS transistors MOB31 and MOB32.

(799) In the case where the semiconductor device described in any of the above embodiments is used in the SAB 3130, the transistor 200 can be used as the OS transistors MO31 and MOB31, and the capacitor 100 can be used as the capacitors C31 and CB31. In this case, the area occupied by one set consisting of a transistor and a capacitor can be reduced when seen from the above; accordingly, the semiconductor device of this embodiment can be highly integrated.

(800) The OS transistors MO31, MO32, MOB31, and MOB32 each include a back gate, and each of these back gates are electrically connected to a power supply line that supplies a fixed voltage.

(801) A gate of the Si transistor M31 corresponds to a node N31, a gate of the OS transistor MO32 corresponds to a node N32, and a gate of the OS transistor MOB32 corresponds to a node NB32.

(802) The nodes N32 and NB32 are each a charge retention node of the CM 3135. The OS transistor MO32 controls the conduction state between the node N31 and a signal line for the signal context[0]. The OS transistor MOB32 controls the conduction state between the node N31 and a low-potential power supply line VSS.

(803) The logics of data retained at the memory circuits 3137 and 3137B have a complementary relationship. Thus, either the OS transistor MO32 or the OS transistor MOB32 is turned on.

(804) The operation example of the PRS 3133[0] is described with reference to FIG. 64(C). In the PRS 3133[0], to which configuration data has already been written, the node N32 is at “H” and the node NB32 is at “L”.

(805) The PRS 3133[0] is inactive while the signal context[0] is at “L”. During this period, even when an input terminal (input) of the PRS 3133[0] is transferred to “H”, the gate of the Si transistor M31 is kept at “L” and an output terminal (output) of the PRS 3133[0] is also kept at “L”.

(806) The PRS 3133[0] is active while the signal context[0] is at “HI”. When the signal context[0] is transferred to “H”, the gate of the Si transistor M31 is transferred to “H” by the configuration data stored in the CM 3135.

(807) When the input terminal is transferred to “H” during the period when the PRS 3133[0] is active, the gate voltage of the Si transistor M31 is increased by boosting because the OS transistor MO32 of the memory circuit 3137 is a source follower. As a result, the OS transistor MO32 of the memory circuit 3137 loses the driving capability, and the gate of the Si transistor M31 is brought into a floating state.

(808) In the PRS 3133 with a multi-context function, the CM 3135 also functions as a multiplexer.

(809) FIG. 65 illustrates a configuration example of the PLE 3121. The PLE 3121 includes an LUT (lookup table) block 3123, a register block 3124, a selector 3125, and a CM 3126. The LUT block 3123 is configured to select and output data in accordance with inputs MA to MD. The selector 3125 selects an output of the LUT block 3123 or an output of the register block 3124 in accordance with the configuration data stored in the CM 3126.

(810) The PLE 3121 is electrically connected to a power supply line for a voltage VDD through a

power switch **3127**. Whether the power switch **3127** is turned on or off is determined in accordance with the configuration data stored in a CM **3128**. Providing the power switch **3127** for each PLE **3121** enables fine-grained power gating. The PLE **3121** that is not used after context switching can be power gated owing to the fine-grained power gating function; thus, standby power can be effectively reduced.

(811) The register block **3124** is formed by nonvolatile registers to achieve NOFF computing. The nonvolatile registers in the PLE **3121** are each a flip-flop provided with an OS memory (hereinafter referred to as an [OS-FF]).

(812) The register block **3124** includes OS-FFs **3140**[1] and **3140**[2]. Signals user_res, load, and store are input to the OS-FFs **3140**[1] and **3140**[2]. A clock signal CLK1 is input to the OS-FF **3140**[1] and a clock signal CLK2 is input to the OS-FF **3140**[2]. FIG. **66**(A) illustrates a configuration example of the OS-FF **3140**.

(813) The OS-FF **3140** includes an FF **3141** and a shadow register **3142**. The FF **3141** includes nodes CK, R, D, Q, and QB. A clock signal is input to the node CK. The signal user_res is input to the node R. The signal user_res is a reset signal. The node D is a data input node, and the node Q is a data output node. The logics of the node Q and the node QB have a complementary relationship.

(814) The shadow register **3142** functions as a backup circuit of the FF **3141**. The shadow register **3142** backs up data of the nodes Q and QB in accordance with the signal store and writes back the backed up data to the nodes Q and QB in accordance with the signal load.

(815) The shadow register **3142** includes inverter circuits **3188** and **3189**, Si transistors M37 and MB37, and memory circuits **3143** and **3143B**. The memory circuits **3143** and **3143B** have the same circuit configuration as the memory circuit **3137** of the PRS **3133**. The memory circuit **3143** includes a capacitor C36 and OS transistors MO35 and MO36. The memory circuit **3143B** includes a capacitor CB36 and OS transistors MOB35 and MOB36. A node N36 and a node NB36 correspond to a gate of the OS transistor MO36 and a gate of the OS transistor MOB36, respectively, and are each a charge retention node. A node N37 and a node NB37 correspond to a gate of the Si transistor M37 and a gate of the Si transistor MB37, respectively.

(816) In the case where the semiconductor device described in any of the above embodiments is used in the LAB **3120**, the transistor **200** can be used as the OS transistors MO35 and MOB35, and the capacitor **100** can be used as the capacitors C36 and CB36. In this case, the area occupied by one set consisting of a transistor and a capacitor can be reduced when seen from the above; accordingly, the semiconductor device of this embodiment can be highly integrated.

(817) The OS transistors MO35, MO36, MOB35, and MOB36 each include a back gate, and each of these back gates are electrically connected to a power supply line that supplies a fixed voltage.

(818) An example of an operation method of the OS-FF **3140** is described with reference to FIG. **66**(B).

(819) (Backup)

(820) When the signal store at “H” is input to the OS-FF **3140**, the shadow register **3142** backs up the data of the FF **3141**. The node N36 becomes “L” when the data of the node Q is written thereto, and the node NB36 becomes “H” when the data of the node QB is written thereto. After that, power gating is performed and the power switch **3127** is turned off. Although the data of the nodes Q and QB of the FF **3141** are lost, the shadow register **3142** retains the backed up data even when power supply is stopped.

(821) (Recovery)

(822) The power switch **3127** is turned on to supply power to the PLE **3121**. After that, when the signal load at “H” is input to the OS-FF **3140**, the shadow register **3142** writes back the backed up data to the FF **3141**. The node N37 is kept at “L” because the node N36 is at “L”, and the node NB37 becomes “H” because the node NB36 is at “H”. Thus, the node Q becomes “H” and the node QB becomes “L”. That is, the OS-FF **3140** is recovered to a state at the backup operation.

(823) A combination of the fine-grained power gating and backup/recovery operation of the OS-FF

3140 allows power consumption of the OS-FPGA **3110** to be effectively reduced.

(824) As an error that might occur in a memory circuit, a soft error due to entry of radiation is given. The soft error is a phenomenon in which a malfunction such as inversion of data stored in a memory is caused by electron-hole pair generation when a transistor is irradiated with a rays emitted from a material of a memory or a package or the like, secondary cosmic ray neutrons generated by nuclear reaction of primary cosmic rays entering the Earth's atmosphere from outer space with nuclei of atoms existing in the atmosphere, or the like. An OS memory using an OS transistor has a high soft-error tolerance. Therefore, the OS-FPGA **3110** with high reliability can be provided when an OS memory is included therein.

(825) The structure described in this embodiment can be used in appropriate combination with the structure described in the other embodiments.

Embodiment 8

(826) In this embodiment, an AI system in which the semiconductor device of any of the above embodiments is used is described with reference to FIG. **67**.

(827) FIG. **67** is a block diagram illustrating a structure example of an AI system **4041**. The AI system **4041** includes an arithmetic portion **4010**, a control portion **4020**, and an input/output portion **4030**.

(828) The arithmetic portion **4010** includes an analog arithmetic circuit **4011**, a DOSRAM **4012**, a NOSRAM **4013**, and an FPGA **4014**. The DOSRAM **1400**, the NOSRAM **1600**, and the OS-FPGA **3110** described in the above embodiments can be used as the DOSRAM **4012**, the NOSRAM **4013**, and the FPGA **4014**, respectively.

(829) The control portion **4020** includes a CPU (Central Processing Unit) **4021**, a GPU (Graphics Processing Unit) **4022**, a PLL (Phase Locked Loop) **4023**, an SRAM (Static Random Access Memory) **4024**, a PROM (Programmable Read Only Memory) **4025**, a memory controller **4026**, a power supply circuit **4027**, and a PMU (Power Management Unit) **4028**.

(830) The input/output portion **4030** includes an external memory control circuit **4031**, an audio codec **4032**, a video codec **4033**, a general-purpose input/output module **4034**, and a communication module **4035**.

(831) The arithmetic portion **4010** can execute learning or inference by a neural network.

(832) The analog arithmetic circuit **4011** includes an A/D (analog/digital) converter circuit, a D/A (digital/analog) converter circuit, and a product-sum operation circuit.

(833) The analog arithmetic circuit **4011** is preferably formed using an OS transistor. The analog arithmetic circuit **4011** using an OS transistor includes an analog memory and can execute a product-sum operation necessary for the learning or inference with low power consumption.

(834) The DOSRAM **4012** is a DRAM formed using an OS transistor, and the DOSRAM **4012** is a memory that temporarily stores digital data sent from the CPU **4021**. The DOSRAM **4012** includes a memory cell including an OS transistor and a read circuit portion including a Si transistor. Because the memory cell and the read circuit portion can be provided in different layers that are stacked, the entire circuit area of the DOSRAM **4012** can be small.

(835) In the calculation with the neural network, the number of input data exceeds **1000** in some cases. In the case where the input data are stored in an SRAM, the input data have to be stored piece by piece because of the circuit area limitation and small storage capacity of the SRAM. The DOSRAM **4012** has a larger storage capacity than an SRAM because the memory cells can be highly integrated even in a limited circuit area. Therefore, the DOSRAM **4012** can efficiently store the input data.

(836) The NOSRAM **4013** is a nonvolatile memory using an OS transistor. The NOSRAM **4013** consumes less power in writing data than the other nonvolatile memories such as a flash memory, a ReRAM (Resistive Random Access Memory), and an MRAM (Magnetoresistive Random Access Memory). Furthermore, unlike a flash memory and a ReRAM in which elements deteriorate by data writing, the NOSRAM has no limitation on the number of times of data writing.

(837) Furthermore, the NOSRAM **4013** can store multilevel data of two or more bits as well as one-bit binary data. The multilevel data storage in the NOSRAM **4013** leads to a reduction in the memory cell area per bit.

(838) Furthermore, the NOSRAM **4013** can store analog data as well as digital data. Thus, the analog arithmetic circuit **4011** can use the NOSRAM **4013** as an analog memory. The NOSRAM **4013** can store analog data as it is, and thus a D/A converter circuit and an A/D converter circuit are unnecessary. Therefore, the area of a peripheral circuit for the NOSRAM **4013** can be reduced. In this specification, analog data refers to data having a resolution of three bits (eight levels) or more. The above-described multilevel data is included in the analog data in some cases.

(839) Data and parameters used in the neural network calculation can be once stored in the NOSRAM **4013**. The data and parameters may be stored in a memory provided outside the AI system **4041** via the CPU **4021**; however, the NOSRAM **4013** provided inside the AI system **4041** can store the data and parameters more quickly with lower power consumption. Furthermore, the NOSRAM **4013** enables a longer bit line than the DOSRAM **4012** and thus can have an increased storage capacity.

(840) The FPGA **4014** is an FPGA using an OS transistor. With the use of the FPGA **4014**, the AI system **4041** can establish a connection of a neural network such as a deep neural network (DNN), a convolutional neural network (CNN), a recurrent neural network (RNN), an autoencoder, a deep Boltzmann machine (DBM), or a deep belief network (DBN) described later, with a hardware. Establishing the connection of the neural network with a hardware enables higher speed performance.

(841) The FPGA **4014** is an FPGA including an OS transistor. An OS-FPGA can have a smaller memory area than an FPGA including an SRAM. Thus, addition of a context switching function only causes a small increase in area. Moreover, an OS-FPGA can transmit data and parameters at high speed by boosting.

(842) In the AI system **4041**, the analog arithmetic circuit **4011**, the DOSRAM **4012**, the NOSRAM **4013**, and the FPGA **4014** can be provided on one die (chip). Thus, the AI system **4041** can execute calculation of the neural network quickly with low power consumption. In addition, the analog arithmetic circuit **4011**, the DOSRAM **4012**, the NOSRAM **4013**, and the FPGA **4014** can be fabricated through the same manufacturing process. Therefore, the AI system **4041** can be fabricated at low cost.

(843) Note that the arithmetic portion **4010** does not necessarily include all of the following: the DOSRAM **4012**, the NOSRAM **4013**, and the FPGA **4014**. One or more memories selected from the DOSRAM **4012**, the NOSRAM **4013**, and the FPGA **4014** are provided in accordance with a problem that is desired to be solved by the AI system **4041**.

(844) The AI system **4041** can execute a method such as a deep neural network (DNN), a convolutional neural network (CNN), a recurrent neural network (RNN), an autoencoder, a deep Boltzmann machine (DBM), or a deep belief network (DBN) in accordance with the problem that is desired to be solved. The PROM **4025** can store a program for executing at least one of these methods. Furthermore, part or the whole of the program may be stored in the NOSRAM **4013**.

(845) Most of the existing programs used as libraries are premised on processing with a GPU. Therefore, the AI system **4041** preferably includes the GPU **4022**. The AI system **4041** can execute the bottleneck product-sum operation among all the product-sum operations used for learning and inference in the arithmetic portion **4010**, and execute the other product-sum operations in the GPU **4022**. In this manner, the learning and inference can be executed at high speed.

(846) The power supply circuit **4027** generates not only a low power supply potential for a logic circuit but also a potential for an analog operation. The power supply circuit **4027** may use an OS memory. When a reference potential is stored in the OS memory, the power consumption of the power supply circuit **4027** can be reduced.

(847) The PMU **4028** has a function of temporarily stopping the power supply to the AI system

4041.

(848) The CPU **4021** and the GPU **4022** preferably include OS memories as registers. By including the OS memories, the CPU **4021** and the GPU **4022** can retain data (logic values) in the OS memories even when power supply is stopped. As a result, the AI system **4041** can save the power.

(849) The PLL **4023** has a function of generating a clock. The AI system **4041** performs an operation on the basis of the clock generated by the PLL **4023**. The PLL **4023** preferably includes an OS memory. By including the OS memory, the PLL **4023** can retain an analog potential with which the clock oscillation frequency is controlled.

(850) The AI system **4041** may store data in an external memory such as a DRAM. For this reason, the AI system **4041** preferably includes the memory controller **4026** functioning as an interface with the external DRAM. Furthermore, the memory controller **4026** is preferably positioned near the CPU **4021** or the GPU **4022**. Thus, data transmission can be performed at high speed.

(851) Some or all of the circuits illustrated in the control portion **4020** can be formed on the same die as the arithmetic portion **4010**. Thus, the AI system **4041** can execute the neural network calculation at high speed with low power consumption.

(852) Data used for the neural network calculation is stored in an external storage device (such as an HDD (Hard Disk Drive) or an SSD (Solid State Drive)) in many cases. Therefore, the AI system **4041** preferably includes the external memory control circuit **4031** functioning as an interface with the external storage device.

(853) Because the neural network often deals with audio and video for learning and inference, the AI system **4041** includes the audio codec **4032** and the video codec **4033**. The audio codec **4032** encodes and decodes audio data, and the video codec **4033** encodes and decodes video data.

(854) The AI system **4041** can perform learning or inference using data obtained from an external sensor. For this reason, the AI system **4041** includes the general-purpose input/output module **4034**. The general-purpose input/output module **4034** includes a USB (Universal Serial Bus) or an I2C (Inter-Integrated Circuit), for example.

(855) The AI system **4041** can perform learning or inference using data obtained via the Internet. For this reason, the AI system **4041** preferably includes the communication module **4035**.

(856) The analog arithmetic circuit **4011** may use a multi-level flash memory as an analog memory. However, the flash memory has a limitation on the number of rewriting times. In addition, it is extremely difficult to embed the multi-level flash memory (to form the arithmetic circuit and the memory on the same die).

(857) Alternatively, the analog arithmetic circuit **4011** may use a ReRAM as an analog memory. However, the ReRAM has a limitation on the number of rewriting times and also has a problem in storage accuracy. Moreover, the ReRAM is a two-terminal element, and thus has a complicated circuit design for separating data writing and data reading.

(858) Further alternatively, the analog arithmetic circuit **4011** may use an MRAM as an analog memory. However, the MRAM has a problem in storage accuracy because of its low magnetoresistive ratio.

(859) In consideration of the above, the analog arithmetic circuit **4011** preferably uses an OS memory as an analog memory.

(860) The structure described in this embodiment can be used in appropriate combination with the structure described in the other embodiments.

Embodiment 9

(861) <Application Example of AI System>

(862) In this embodiment, application examples of the AI system described in the above embodiment is described with reference to FIG. **68**.

(863) FIG. **68(A)** is an AI system **4041A** in which the AI systems **4041** described with FIG. **67** are arranged in parallel and a signal can be transmitted between the systems via a bus line.

(864) The AI system **4041A** illustrated in FIG. **68(A)** includes a plurality of AI systems **4041_1** to

4041_n (n is a natural number). The AI system **4041₁** to the AI system **4041_n** are connected to each other via a bus line **4098**.

(865) FIG. **68(B)** is an AI system **4041B** in which the AI systems **4041** described with FIG. **67** are arranged in parallel as in FIG. **68(A)** and a signal can be transmitted between the systems via a network.

(866) The AI system **4041B** illustrated in FIG. **68(B)** includes the plurality of AI systems **4041₁** to **4041_n**. The AI system **4041₁** to the AI system **4041_n** are connected to each other via a network **4099**.

(867) A structure may be employed in which a communication module is provided in each of the AI system **4041₁** to the AI system **4041_n** to perform wireless or wired communication via the network **4099**. A communication module can perform communication via an antenna. For example, the communication can be performed in such a manner that an electronic device is connected to a computer network such as the Internet that is an infrastructure of the World Wide Web (WWW), an intranet, an extranet, a PAN (Personal Area Network), a LAN (Local Area Network), a CAN (Campus Area Network), a MAN (Metropolitan Area Network), a WAN (Wide Area Network), or a GAN (Global Area Network). In the case of performing wireless communication, it is possible to use, as a communication protocol or a communication technology, a communications standard such as LTE (Long Term Evolution), GSM (Global System for Mobile Communication: registered trademark), EDGE (Enhanced Data Rates for GSM Evolution), CDMA 2000 (Code Division Multiple Access 2000), or W-CDMA (registered trademark), or a communications standard developed by IEEE such as Wi-Fi (registered trademark), Bluetooth (registered trademark), or ZigBee (registered trademark).

(868) With the structure illustrated in FIG. **68(A)** or **68(B)**, analog signals obtained with external sensors or the like can be processed by different AI systems. For example, biological information such as brain waves, a pulse, blood pressure, and body temperature is obtained with a variety of sensors such as a brain wave sensor, a pulse wave sensor, a blood pressure sensor, and a temperature sensor, and analog signals can be processed by different AI systems. When the signal processing or learning is performed by different AI systems, the amount of information processed by each AI system can be reduced. Accordingly, the signal processing or learning can be performed with a smaller amount of arithmetic processing. As a result, recognition accuracy can be increased. The information obtained with each AI system is expected to enable instant understanding of collective biological information that irregularly changes.

(869) The structure described in this embodiment can be used in appropriate combination with the structure described in the other embodiments.

Embodiment 10

(870) In this embodiment, an example of an IC incorporating the AI system described in the above embodiment is described.

(871) In the AI system described in the above embodiment, a digital processing circuit such as a CPU that includes a Si transistor, an analog arithmetic circuit that uses an OS transistor, an OS-FPGA, and an OS memory such as a DOSRAM or a NOSRAM can be integrated into one die.

(872) FIG. **69** illustrates the example of the IC incorporating the AI system. An AI system IC **7000** illustrated in FIG. **69** includes a lead **7001** and a circuit portion **7003**. The AI system IC **7000** is mounted on a printed circuit board **7002**, for example. A plurality of such IC chips are combined and electrically connected to each other on the printed circuit board **7002**; thus, a board on which electronic components are mounted (a circuit board **7004**) is completed. In the circuit portion **7003**, the various circuits described in the above embodiment are provided on one die. The circuit portion **7003** has a stacked-layer structure, which is broadly divided into a Si transistor layer **7031**, a wiring layer **7032**, and an OS transistor layer **7033**. Since the OS transistor layer **7033** can be provided to be stacked over the Si transistor layer **7031**, the size of the AI system IC **7000** can be easily reduced.

(873) Although a QFP (Quad Flat Package) is used as a package of the AI system IC **7000** in FIG. **69**, the embodiment of the package is not limited thereto.

(874) The digital processing circuit such as a CPU, the analog arithmetic circuit that uses an OS transistor, the OS-FPGA, and the OS memory such as a DOSRAM or a NOSRAM can all be formed in the Si transistor layer **7031**, the wiring layer **7032**, and the OS transistor layer **7033**. In other words, elements included in the AI system can be formed through the same manufacturing process. Thus, the number of steps in the manufacturing process of the IC described in this embodiment does not need to be increased even when the number of elements is increased, and accordingly the AI system can be incorporated into the IC at low cost.

(875) The structure described in this embodiment can be used in appropriate combination with the structure described in the other embodiments.

Embodiment 11

(876) <Electronic Device>

(877) A semiconductor device of one embodiment of the present invention can be used for a variety of electronic devices. FIG. **70** illustrates specific examples of electronic devices including the semiconductor device of one embodiment of the present invention.

(878) FIG. **70(A)** illustrates a monitor **830**. The monitor **830** includes a display portion **831**, a housing **832**, a speaker **833**, and the like. The monitor **830** can also include an LED lamp, operation keys (including a power switch or an operation switch), a connection terminal, a variety of sensors, a microphone, and the like. The monitor **830** can be controlled with a remote controller **834**.

(879) The monitor **830** can function as a television device by receiving airwaves.

(880) Examples of airwaves that the monitor **830** can receive include a ground wave and a radio wave transmitted from a satellite. Examples of airwaves also include airwaves for analog broadcasting, digital broadcasting, image-and-sound broadcasting, and sound-only broadcasting. For example, the monitor **830** can receive airwaves transmitted in a certain frequency band in a UHF band (higher than or equal to 300 MHz and lower than or equal to 3 GHz) or a VHF band (higher than or equal to 30 MHz and lower than or equal to 300 MHz). With the use of a plurality of pieces of data received in a plurality of frequency bands, the transfer rate can be increased and more information can thus be obtained, for example. Accordingly, the display portion **831** can display an image with a resolution higher than the full high definition. For example, an image with a resolution of 4K2K, 8K4K, 16K8K, or more can be displayed.

(881) An image to be displayed on the display portion **831** may be generated using broadcasting data transmitted with a technology for transmitting data via a computer network such as the Internet, a LAN (Local Area Network), or Wi-Fi (registered trademark). In that case, the monitor **830** does not need to include a tuner.

(882) The monitor **830** can be used as a computer monitor when connected to a computer. Several people can see the monitor **830** connected to a computer at the same time; thus, the monitor **830** can be used for a conference system. The monitor **830** can also be used for a videoconference system by displaying data in a computer via a network or being directly connected to a network.

(883) Alternatively, the monitor **830** can be used as a digital signage.

(884) The semiconductor device of one embodiment of the present invention can be used for, for example, a driver circuit or an image processing portion of the display portion. When the semiconductor device of one embodiment of the present invention is used for a driver circuit or an image processing portion of the display portion, high-speed operation or high-speed signal processing can be achieved with low power consumption.

(885) When an AI system including the semiconductor device of one embodiment of the present invention is used for the image processing portion of the monitor **830**, image processing such as noise removal processing, grayscale conversion processing, tone correction processing, or luminance correction processing can be performed. Furthermore, pixel interpolation processing due to resolution up-conversion, frame interpolation processing due to frame frequency up-conversion,

or the like can be performed. In the grayscale conversion processing, not only change of the number of grayscale levels of an image but also interpolation of the gray value in the case of increasing the number of grayscale levels can be performed. In addition, high-dynamic range (HDR) processing for increasing a dynamic range is also included in the grayscale conversion processing.

(886) A video camera **2940** illustrated in FIG. 70(B) includes a housing **2941**, a housing **2942**, a display portion **2943**, operation switches **2944**, a lens **2945**, a joint **2946**, and the like. The operation switches **2944** and the lens **2945** are provided on the housing **2941**, and the display portion **2943** is provided on the housing **2942**. The video camera **2940** also includes an antenna, a battery, and the like inside the housing **2941**. The housing **2941** and the housing **2942** are connected to each other with the joint **2946**, and the angle between the housing **2941** and the housing **2942** can be changed with the joint **2946**. Depending on the angle between the housing **2941** and the housing **2942**, the orientation of an image displayed on the display portion **2943** can be changed or display and non-display of an image can be switched.

(887) The semiconductor device of one embodiment of the present invention can be used for, for example, a driver circuit or an image processing portion of the display portion. When the semiconductor device of one embodiment of the present invention is used for a driver circuit or an image processing portion of the display portion, high-speed operation or high-speed signal processing can be achieved with low power consumption.

(888) When an AI system including the semiconductor device of one embodiment of the present invention is used for the image processing portion of the video camera **2940**, imaging appropriate for the surroundings of the video camera **2940** can be performed. Specifically, imaging can be performed with optimal exposure for the surrounding brightness. In the case of performing imaging with backlighting or imaging under different brightness conditions such as indoors and outdoors at the same time, high-dynamic-range (HDR) imaging can be performed.

(889) Furthermore, the AI system can learn user's habit and assist the user in performing imaging. Specifically, the AI system can learn user's camera shaking habit and cancel the camera shaking during imaging, so that blurring of the obtained image associated with camera shaking can be reduced as much as possible. In the case of using a zoom function during imaging, the orientation of a lens or the like can be controlled such that a subject is positioned at the center of an image all the time.

(890) An information terminal **2910** illustrated in FIG. 70(C) includes a housing **2911**, a display portion **2912**, a microphone **2917**, a speaker portion **2914**, a camera **2913**, an external connection portion **2916**, operation switches **2915**, and the like. A touch screen and a display panel formed using flexible substrates are provided in the display portion **2912**. The information terminal **2910** also includes an antenna, a battery, and the like inside the housing **2911**. The information terminal **2910** can be used as, for example, a smartphone, a mobile phone, a tablet information terminal, a tablet personal computer, or an e-book reader.

(891) A memory device including the semiconductor device of one embodiment of the present invention can retain control data or a control program of the information terminal **2910** for a long time, for example.

(892) When an AI system including the semiconductor device of one embodiment of the present invention is used for an image processing portion of the information terminal **2910**, image processing such as noise removal processing, grayscale conversion processing, tone correction processing, or luminance correction processing can be performed. Furthermore, pixel interpolation processing due to resolution up-conversion, frame interpolation processing due to frame frequency up-conversion, or the like can be performed. In the grayscale conversion processing, not only change of the number of grayscale levels of an image but also interpolation of the gray value in the case of increasing the number of grayscale levels can be performed. In addition, high-dynamic range (HDR) processing for increasing a dynamic range is also included in the grayscale

conversion processing.

(893) Furthermore, the AI system can learn user's habit and assist the user in operating the information terminal **2910**. The information terminal **2910** incorporating the AI system can predict touch input from the motion of user's fingers, eyes, or the like.

(894) A laptop personal computer **2920** illustrated in FIG. **70(D)** includes a housing **2921**, a display portion **2922**, a keyboard **2923**, a pointing device **2924**, and the like. The laptop personal computer **2920** also includes an antenna, a battery, and the like inside the housing **2921**.

(895) A memory device including the semiconductor device of one embodiment of the present invention can retain control data or a control program of the laptop personal computer **2920** for a long time, for example.

(896) When an AI system including the semiconductor device of one embodiment of the present invention is used for an image processing portion of the laptop personal computer **2920**, image processing such as noise removal processing, grayscale conversion processing, tone correction processing, or luminance correction processing can be performed. Furthermore, pixel interpolation processing due to resolution up-conversion, frame interpolation processing due to frame frequency up-conversion, or the like can be performed. In the grayscale conversion processing, not only change of the number of grayscale levels of an image but also interpolation of the gray value in the case of increasing the number of grayscale levels can be performed. In addition, high-dynamic range (HDR) processing for increasing a dynamic range is also included in the grayscale conversion processing.

(897) Furthermore, the AI system can learn user's habit and assist the user in operating the laptop personal computer **2920**. The laptop personal computer **2920** incorporating the AI system can predict touch input to the display portion **2922**, from the motion of user's fingers, eyes, or the like. In inputting text, the AI system predicts input from the past input text data or a text or a diagram such as a photograph around the text to be input, to assist conversion. Accordingly, input mistakes and conversion mistakes can be reduced as much as possible.

(898) FIG. **70(E)** is an external view illustrating an example of an automobile, and FIG. **70(F)** illustrates a navigation device **860**. An automobile **2980** includes a car body **2981**, wheels **2982**, a dashboard **2983**, lights **2984**, and the like. The automobile **2980** also includes an antenna, a battery, and the like. The navigation device **860** includes a display portion **861**, operation buttons **862**, and an external input terminal **863**. The automobile **2980** and the navigation device **860** can be independent of each other; however, it is preferable that the navigation device **860** be incorporated into and linked to the automobile **2980**.

(899) A memory device including the semiconductor device of one embodiment of the present invention can retain control data or a control program of the automobile **2980** or the navigation device **860** for a long time, for example. When an AI system including the semiconductor device of one embodiment of the present invention is used for a control device or the like of the automobile **2980**, the AI system can learn driver's driving skill and habit and assist the driver in safe driving or driving involving efficient use of fuel such as gasoline or a battery. To assist the driver in safe driving, the AI system learns not only driver's driving skill and habit, but also learns the behavior of the automobile such as the speed and movement of the automobile **2980**, road information saved in the navigation device **860**, and the like complexly; thus, driving lane departure and collision with other automobiles, pedestrians, objects, and the like can be prevented. Specifically, when there is a sharp curve ahead, the navigation device **860** transmits the road information to the automobile **2980** so that the speed of the automobile **2980** can be controlled and steering can be assisted.

(900) This embodiment can be implemented in an appropriate combination with the structures described in the other embodiments, examples, and the like.

REFERENCE NUMERALS

(901) **100** capacitor, **130** conductor, **200** transistor, **203** conductor, **203a** conductor, **203b** conductor, **205** conductor, **205a** conductor, **205b** conductor, **208** insulator, **210** insulator, **216** insulator, **220**

insulator, **222** insulator, **224** insulator, **230** oxide, **230a** oxide, **230b** oxide, **230c** oxide, **231** region, **231a** region, **231b** region, **232** region, **232a** region, **232b** region, **234** region, **239** region, **250** insulator, **250a** insulator, **252** conductor, **252a** conductor, **252b** conductor, **252c** conductor, **252d** conductor, **256** conductor, **260** conductor, **260a** conductor, **260b** conductor, **270** insulator, **271** insulator, **272** insulator, **274** insulator, **280** insulator, **600** cell

Claims

1. A semiconductor device comprising: a substrate; a first insulator over the substrate; a first conductor and a second conductor over the first insulator; a third conductor over the first conductor and the second conductor; a second insulator over the third conductor; an oxide over the second insulator; a third insulator over the oxide; a fourth conductor over the third insulator; a fourth insulator over the fourth conductor; a fifth conductor over the fourth insulator; and a fifth insulator over the fifth conductor, wherein the third conductor comprises a region configured to function as a first gate electrode of a transistor, wherein the fourth conductor comprises a region configured to function as a second gate electrode of the transistor, wherein the oxide comprises a first region configured to function as a channel formation region of the transistor and a second region configured to function as a first electrode of a capacitor, wherein the fifth conductor comprises a region configured to function as a second electrode of the capacitor, wherein the oxide overlaps with the first conductor, wherein the oxide is electrically connected to the second conductor, and wherein the fifth conductor overlaps with the first conductor, the second conductor, the third conductor, and the fourth conductor.
2. The semiconductor device according to claim 1, wherein the oxide comprises In, Ga, and Zn.
3. The semiconductor device according to claim 1, wherein the first conductor is configured to function as a wiring.
4. A semiconductor device comprising: a first transistor; a second transistor; a third transistor; and a first capacitor, wherein a first channel formation region of the first transistor comprises silicon, wherein a first insulator is provided over the first channel formation region, wherein a first conductor is provided over the first insulator, wherein the first conductor comprises a region configured to function as a first gate electrode of the first transistor, wherein a second insulator is provided over the first conductor, wherein a second conductor and a third conductor are provided over the second insulator, wherein a third insulator is provided over the second conductor and the third conductor, wherein an oxide is provided over the third insulator, wherein the oxide comprises a first region configured to function as a second channel formation region of the second transistor, a second region configured to function as a third channel formation region of the third transistor, and a third region configured to function as a first electrode of the first capacitor, wherein a fourth insulator is provided over the oxide, wherein a fourth conductor is provided over the fourth insulator, wherein a fifth conductor is provided over the oxide, wherein a fifth insulator is provided over the fourth conductor and the fifth conductor, wherein a sixth conductor is provided over the fifth insulator, wherein the sixth conductor comprises a region configured to function as a second electrode of the first capacitor, and wherein the first conductor is electrically connected to the first electrode of the first capacitor.
5. The semiconductor device according to claim 4, wherein the sixth conductor overlaps with the first channel formation region of the first transistor and the second channel formation region of the second transistor.
6. A semiconductor device comprising: a first transistor; a second transistor; a third transistor; a fourth transistor; and a first capacitor, wherein a first channel formation region of the first transistor comprises silicon, wherein a second channel formation region of the second transistor comprises silicon, wherein a first oxide is provided over the first transistor and the second transistor, wherein a second oxide is provided over the third transistor, wherein the first oxide comprises a first region

configured to function as a third channel formation region of the third transistor, wherein the second oxide comprises a first region configured to function as a fourth channel formation region of the fourth transistor and a second region configured to function as a first electrode of the first capacitor, wherein a first insulator is provided over the second oxide, and wherein a first conductor comprising a region configured to function as a second electrode of the first capacitor is provided over the first insulator.

7. The semiconductor device according to claim 6, further comprising: a second capacitor, wherein the first oxide comprises a second region configured to function as a first electrode of the second capacitor, wherein a first gate electrode of the first transistor is electrically connected to the first electrode of the first capacitor, and wherein a second gate electrode of the second transistor is electrically connected to the first electrode of the second capacitor.
