

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12408451
Kind Code	B2
Date of Patent	September 02, 2025
Inventor(s)	Umebayashi; Taku et al.

Semiconductor device, solid-state imaging device and electronic apparatus

Abstract

A semiconductor device including a first semiconductor section including a first wiring layer at one side thereof, the first semiconductor section further including a photodiode, a second semiconductor section including a second wiring layer at one side thereof, the first and second semiconductor sections being secured together, a third semiconductor section including a third wiring layer at one side thereof, the second and the third semiconductor sections being secured together such the first semiconductor section, second semiconductor section, and the third semiconductor section are stacked together, and a first conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication.

Inventors: Umebayashi; Taku (Kanagawa, JP), Tatani; Keiji (Kanagawa, JP), Inoue; Hajime (Kanagawa, JP), Kanamura; Ryuichi (Kumamoto, JP)

Applicant: SONY GROUP CORPORATION (Tokyo, JP)

Family ID: 49474660

Assignee: Sony Group Corporation (Tokyo, JP)

Appl. No.: 18/520273

Filed: November 27, 2023

Prior Publication Data

Document Identifier	Publication Date
US 20240096925 A1	Mar. 21, 2024

Foreign Application Priority Data

JP	2012-230805	Oct. 18, 2012
JP	2013-089580	Apr. 22, 2013

Related U.S. Application Data

continuation parent-doc US 17719554 20220413 US 11875989 child-doc US 18520273
continuation parent-doc US 17068783 20201012 US 11374049 20220628 child-doc US 17719554
continuation parent-doc US 16555067 20190829 US 10840290 20201117 child-doc US 17068783
continuation parent-doc US 16373105 20190402 US 10475845 20191112 child-doc US 16555067
continuation parent-doc US 16042094 20180723 US 10535700 20200114 child-doc US 16373105
continuation parent-doc US 15852468 20171222 US 10128301 20181113 child-doc US 16042094
continuation parent-doc US 15403154 20170110 US 9917131 20180313 child-doc US 15852468
continuation parent-doc US 15087894 20160331 US 9570499 20170214 child-doc US 15403154
continuation parent-doc US 14434288 US 9431450 20160830 WO PCT/JP2013/006055 20131010
child-doc US 15087894

Publication Classification

Int. Cl.: H10F39/18 (20250101); H10F39/00 (20250101); H10F39/12 (20250101)

U.S. Cl.:

CPC H10F39/182 (20250101); H10F39/018 (20250101); H10F39/18 (20250101);
H10F39/199 (20250101); H10F39/8037 (20250101); H10F39/8053 (20250101);
H10F39/8057 (20250101); H10F39/8063 (20250101); H10F39/809 (20250101);
H10F39/811 (20250101);

Field of Classification Search

CPC: H10F (39/182); H10F (39/018); H10F (39/18); H10F (39/199); H10F (39/8037); H10F
(39/8053); H10F (39/8057); H10F (39/8063); H10F (39/809); H10F (39/811)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9007503	12/2014	Oike	348/308	H04N 25/772
9136163	12/2014	Kumano	N/A	N/A
9252169	12/2015	Kobayashi	N/A	N/A
9385152	12/2015	Endo et al.	N/A	N/A
9431450	12/2015	Umebayashi et al.	N/A	N/A
9570499	12/2016	Umebayashi et al.	N/A	N/A
9917131	12/2017	Umebayashi et al.	N/A	N/A
10128301	12/2017	Umebayashi et al.	N/A	N/A
10475845	12/2018	Umebayashi et al.	N/A	N/A

10535700	12/2019	Umebayashi et al.	N/A	N/A
10840290	12/2019	Umebayashi et al.	N/A	N/A
11374049	12/2021	Umebayashi et al.	N/A	N/A
2009/0224345	12/2008	Lee et al.	N/A	N/A
2010/0026865	12/2009	Tivarus et al.	N/A	N/A
2010/0038802	12/2009	Chen et al.	N/A	N/A
2010/0276572	12/2009	Iwabuchi et al.	N/A	N/A
2011/0049336	12/2010	Matsunuma	257/431	H01L 27/14692
2011/0168434	12/2010	Farooq	174/257	H01L 21/2007
2012/0056288	12/2011	Yoshihara et al.	N/A	N/A
2012/0062777	12/2011	Shoji et al.	N/A	N/A
2012/0199930	12/2011	Toshihko	N/A	N/A
2012/0241981	12/2011	Hirano	257/777	H01L 23/562
2013/0221473	12/2012	Shimotsusa et al.	N/A	N/A
2013/0307103	12/2012	Lin et al.	N/A	N/A
2014/0048853	12/2013	Choi et al.	N/A	N/A
2015/0035109	12/2014	Kataoka	N/A	N/A
2015/0091066	12/2014	Lee	257/369	H01L 25/0657
2018/0323231	12/2017	Saito	N/A	N/A
2022/0246668	12/2021	Umebayashi et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101355067	12/2008	CN	N/A
102054849	12/2010	CN	N/A
102110700	12/2010	CN	N/A
2426718	12/2011	EP	N/A
2426719	12/2011	EP	N/A
2001-339057	12/2000	JP	H01L 27/146
2006-147749	12/2005	JP	N/A
2007-228460	12/2006	JP	N/A
2009-176777	12/2008	JP	N/A
2010-245506	12/2009	JP	N/A
2011-096851	12/2010	JP	N/A
2011-049445	12/2010	JP	N/A
2012-015278	12/2011	JP	N/A
2012-033894	12/2011	JP	N/A
2012-054450	12/2011	JP	N/A
2012-054876	12/2011	JP	N/A
2012-064709	12/2011	JP	N/A

2012-164870	12/2011	JP	N/A
10-2001-0006328	12/2000	KR	N/A
10-2008-0019652	12/2007	KR	N/A
10-2011-0023758	12/2010	KR	N/A
200709407	12/2006	TW	N/A
200803484	12/2007	TW	N/A
WO 2006/129762	12/2005	WO	N/A
WO 2007/105478	12/2006	WO	N/A

OTHER PUBLICATIONS

International Search Report prepared by the European Patent Office on Jan. 20, 2014, for International Application No. PCT/JP2013/006055. cited by applicant

Official Action (no English translation available) for Japanese Patent Application No. 2013-089580 mailed Jan. 26, 2017, 18 pages. cited by applicant

Official Action (no English translation available) for Japanese Patent Application No. 2013-089580 mailed Apr. 4, 2017. 5 pages. cited by applicant

Official Action (with English translation) for Chinese Patent Application No. 201380053203.0 dated Jan. 23, 2017, 19 pages. cited by applicant

Official Action (no English translation available) for Japanese Patent Application No. 2013-089580 dated Aug. 14, 2017, 11 pages. cited by applicant

Official Action for European Patent Application No. 13780221.1 dated Nov. 23, 2017, 8 pages. cited by applicant

Official Action (no translation available) for Japanese Patent Application No. 2017-091571, dated Mar. 15, 2018, 10 pages. cited by applicant

Official Action (no translation available) for Japanese Patent Application No. 2013-089580, dated Mar. 29, 2018, 33 pages. cited by applicant

Official Action (no translation available) for Japanese Patent Application No. 2018-139958, dated May 9, 2019, 3 pages. cited by applicant

Extended European Search Report for European Patent Application No. 19195353.8, dated Dec. 18, 2019, 13 pages. cited by applicant

Official Action (no English translation) for Japanese Patent Application No. 2018-139958, dated Jan. 7, 2020, 5 pages. cited by applicant

Official Action (with English translation) for Korean Patent Application No. 10-2015-7008512, dated Jan. 28, 2020, 13 pages. cited by applicant

Official Action for U.S. Appl. No. 14/434,288, dated Nov. 17, 2015, 15 pages. cited by applicant
Notice of Allowance for U.S. Appl. No. 14/434,288, dated Apr. 26, 2016, 7 pages. cited by applicant

Official Action for U.S. Appl. No. 15/087,894, dated May 20, 2016, 10 pages. cited by applicant
Notice of Allowance for U.S. Appl. No. 15/087,894, dated Sep. 28, 2016, 8 pages. cited by applicant

Official Action for U.S. Appl. No. 15/403,154, dated Mar. 8, 2017, 6 pages. cited by applicant
Notice of Allowance for U.S. Appl. No. 15/403,154, dated Oct. 24, 2017, 8 pages. cited by applicant

Official Action for U.S. Appl. No. 15/852,468, dated Mar. 9, 2018, 7 pages. cited by applicant
Notice of Allowance for U.S. Appl. No. 15/852,468, dated Jul. 2, 2018, 7 pages. cited by applicant
Official Action for U.S. Appl. No. 16/042,094, dated Apr. 18, 2019, 7 pages. cited by applicant

Notice of Allowance for U.S. Appl. No. 16/042,094, dated Aug. 14, 2019, 7 pages. cited by applicant

Notice of Allowance for U.S. Appl. No. 16/373,105, dated Jul. 8, 2019, 10 pages. cited by applicant

Official Action for U.S. Appl. No. 16/555,067, dated May 14, 2020, 6 pages. cited by applicant

Notice of Allowance for U.S. Appl. No. 16/555,067, dated Jul. 16, 2020, 8 pages. cited by applicant
Notice of Allowance for U.S. Appl. No. 17/068,783, dated Feb. 18, 2022, 9 pages. cited by applicant
Official Action for U.S. Appl. No. 17/719,554, dated Apr. 12, 2023, 11 pages. cited by applicant
Notice of Allowance for U.S. Appl. No. 17/719,554, dated Aug. 31, 2023, 5 pages. cited by applicant

Primary Examiner: Nguyen; Dao H

Attorney, Agent or Firm: SHERIDAN ROSS P.C.

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS (1) This application is a continuation of U.S. patent application Ser. No. 17/719,554, filed Apr. 13, 2022, which is a continuation of U.S. patent application Ser. No. 17/068,783, filed Oct. 12, 2020, now U.S. Pat. No. 11,374,049, which is a continuation of U.S. patent application Ser. No. 16/555,067, filed Aug. 29, 2019, now U.S. Pat. No. 10,840,290, which is a continuation of U.S. patent application Ser. No. 16/373,105, filed Apr. 2, 2019, now U.S. Pat. No. 10,475,845, which is a continuation of U.S. patent application Ser. No. 16/042,094, filed Jul. 23, 2018, now U.S. Pat. No. 10,535,700, which is a continuation of U.S. patent application Ser. No. 15/852,468, filed Dec. 22, 2017, now U.S. Pat. No. 10,128,301, which is a continuation of U.S. patent application Ser. No. 15/403,154, filed Jan. 10, 2017, now U.S. Pat. No. 9,917,131, which is a continuation of U.S. patent application Ser. No. 15/087,894, filed Mar. 31, 2016, now U.S. Pat. No. 9,570,499, which is a continuation of U.S. patent application Ser. No. 14/434,288, filed Apr. 8, 2015, now U.S. Pat. No. 9,431,450, which is a national stage application under 35 U.S.C. 371 and claims the benefit of PCT Application No. PCT/JP2013/006055, filed Oct. 10, 2013, which claims priority to Japanese Patent Application Nos. JP 2012-230805 and JP 2013-089580, filed in the Japan Patent Office on Oct. 18, 2012, and Apr. 22, 2013, respectively, the entire disclosures of which are hereby incorporated herein by reference.

TECHNICAL FIELD

(1) The present technology relates to a solid-state imaging device, and particularly to a solid-state imaging device capable of easily providing a high-quality stacked image sensor.

BACKGROUND ART

(2) As solid-state imaging devices, there is an amplification type solid-state imaging device represented by a MOS type image sensor such as a complementary metal oxide semiconductor (CMOS). In addition, there is a charge transfer type solid-state imaging device represented by a charge coupled device (CCD) image sensor.

(3) These solid-state imaging devices are frequently used in digital still cameras, digital video cameras, and the like. In recent years, as solid-state imaging devices have been mounted in mobile apparatuses, such as mobile phones and personal digital assistants (PDAs) with cameras, a MOS type image sensor has been frequently used from the viewpoint of having a low power supply voltage, low power consumption, and the like.

(4) The MOS type solid-state imaging device includes a pixel array (pixel region) in which a plurality of unit pixels are arranged in a two-dimensional array form and a peripheral circuit region, and each of the unit pixels includes a photo diode which is a photoelectric conversion portion and a plurality of pixel transistors. A plurality of pixel transistors are formed of MOS transistors, and generally comprise three transistors including a transfer transistor, a reset transistor, an amplification transistor, or four transistors additionally including a selection transistor.

- (5) In addition, in the above-described solid-state imaging device, a stacked structure has been proposed in which a plurality of semiconductor substrates having different functions are stacked in an overlapping manner and are electrically connected to each other.
- (6) In the stacked structure, since each circuit can be formed optimally so as to correspond to the function of each semiconductor substrate, it is possible to easily realize high performance of a device.
- (7) For example, it is possible to manufacture a high performance solid-state imaging device by optimally forming a sensor circuit and a logical circuit so as to correspond to respective functions of a semiconductor substrate including the sensor circuit and a semiconductor substrate including the logical circuit in which a circuit processing signal is provided. At this time, through electrodes are provided in substrates of the semiconductor substrates, and thereby the plurality of semiconductor substrates are electrically connected to each other.
- (8) However, if a semiconductor device is formed by connecting different substrates to each other by using a connection conductor which penetrates through a substrate, it is necessary to form a connection hole while maintaining insulation in the deep substrate, and thus a practical use is difficult from the viewpoint of economic costs of a manufacturing process which is necessary in creating the connection hole and embedding the connection conductor.
- (9) On the other hand, for example, if a small contact hole of about 1 micrometer is to be formed, it is necessary to thin an upper substrate to the utmost limit. In this case, complex steps such as, attaching the upper substrate to a support substrate before being thinned and an increase in costs may result. In addition, in order to embed a connection conductor in a connection hole with a high aspect ratio, a CVD film having a good coatability property, such as tungsten (W), is necessarily used as a connection conductor, and thus materials to be used as a connection conductor may be limited.
- (10) Therefore, a manufacturing method of a semiconductor device such as a solid-state imaging device has been proposed which achieves a high performance by sufficiently exhibiting each performance, mass productivity, and a reduction in costs (for example, refer to PTL 1).
- (11) PTL 1 has proposed a stacked structure in which a support substrate of a rear surface type image sensor is stacked as a logical circuit, and a plurality of connection contacts are provided from the top by using a thinning step of the image sensor.

CITATION LIST

Patent Literature

(12) [PTL 1]

(13) Japanese Unexamined Patent Application Publication No. 2010-245506

SUMMARY OF INVENTION

Technical Problem

(14) It is desirable to easily provide a high-quality stacked image sensor.

Solution to Problem

(15) In accordance with at least one embodiment of the present invention, a semiconductor device is provided, the semiconductor device comprising a first semiconductor section including a first wiring layer at one side thereof, the first semiconductor section further including a photodiode, a second semiconductor section including a second wiring layer at one side thereof, the first and second semiconductor sections being secured together, a third semiconductor section including a third wiring layer at one side thereof, the second and the third semiconductor sections being secured together such the first semiconductor section, second semiconductor section, and the third semiconductor section are stacked together, and a first conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication.

(16) In accordance with at least one embodiment of the present invention, a backside illumination type solid-state imaging device is provided, the solid-state imaging device comprising a first

semiconductor section including a first wiring layer at one side thereof, the first semiconductor section further including a circuit region and a pixel region, a second semiconductor section including a second wiring layer at one side thereof, the first and second semiconductor sections being secured together, a third semiconductor section including a third wiring layer at one side thereof, the second and the third semiconductor sections being secured together such the first semiconductor section, second semiconductor section, and the third semiconductor section are stacked together, and a first conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication.

(17) In accordance with at least one embodiment of the present invention, an electronic apparatus is provided, the electronic apparatus comprising an optical unit, and a solid-state imaging device, the solid state image device including a first semiconductor section including a first wiring layer at one side thereof, the first semiconductor section further including a circuit region and a pixel region, a second semiconductor section including a second wiring layer at one side thereof, the first and second semiconductor sections being secured together, a third semiconductor section including a third wiring layer at one side thereof, the second and the third semiconductor sections being secured together such the first semiconductor section, second semiconductor section, and the third semiconductor section are stacked together, and a first conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication.

(18) Other systems, methods, features, and advantages of the present invention will be or will become apparent to one with skill in the art upon examination of the following figures and detailed description. It is intended that all such additional systems, methods, features, and advantages be within this description, be within the scope of the invention, and be protected by the accompanying claims.

Advantageous Effects of the Invention

(19) According to the present technology, it is possible to easily provide a high-quality stacked image sensor.

Description

BRIEF DESCRIPTION OF DRAWINGS

- (1) FIG. 1 is a cross-sectional view illustrating a configuration of a pixel portion of a stacked solid-state imaging device in the related art.
- (2) FIG. 2 is a cross-sectional view illustrating another configuration of the pixel portion of the stacked solid-state imaging device in the related art.
- (3) FIG. 3 is a diagram illustrating a manufacturing method of a three-layer stacked solid-state imaging device.
- (4) FIG. 4 is a diagram illustrating a manufacturing method of the three-layer stacked solid-state imaging device.
- (5) FIG. 5 is a cross-sectional view illustrating a configuration of a pixel portion of a solid-state imaging device with a three-layer stacked structure manufactured according to FIGS. 3 and 4.
- (6) FIG. 6 is a cross-sectional view illustrating a configuration according to an embodiment of a pixel portion of a solid-state imaging device to which the present technology is applied.
- (7) FIG. 7A is an enlarged view in the vicinity of the pad hole.
- (8) FIG. 7B is a diagram in which the aluminum pad is viewed from the top of the pad hole.
- (9) FIG. 8 is a cross-sectional view illustrating a configuration according to another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.
- (10) FIG. 9 is a cross-sectional view illustrating a configuration according to still another

embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(11) FIG. **10** is a diagram illustrating a schematic configuration of a solid-state imaging device to which the present technology is applied.

(12) FIG. **11** is a schematic diagram of the cross-sectional view related to the configuration of the pixel portion of the solid-state imaging device shown in FIG. **6**.

(13) FIG. **12** is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(14) FIG. **13** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **12**.

(15) FIG. **14** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **12**.

(16) FIG. **15** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **12**.

(17) FIG. **16** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **12**.

(18) FIG. **17** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **12**.

(19) FIG. **18** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **12**.

(20) FIG. **19** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **12**.

(21) FIG. **20** is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(22) FIG. **21** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **20**.

(23) FIG. **22** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **20**.

(24) FIG. **23** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **20**.

(25) FIG. **24** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **20**.

(26) FIG. **25** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **20**.

(27) FIG. **26** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **20**.

(28) FIG. **27** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **20**.

(29) FIG. **28** is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(30) FIG. **29** is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(31) FIG. **30** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **29**.

(32) FIG. **31** is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. **29**.

(33) FIG. 32 is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. 29.

(34) FIG. 33 is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. 29.

(35) FIG. 34 is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. 29.

(36) FIG. 35 is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(37) FIG. 36 is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. 35.

(38) FIG. 37 is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. 35.

(39) FIG. 38 is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. 35.

(40) FIG. 39 is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. 35.

(41) FIG. 40 is a diagram illustrating a manufacturing process of the solid-state imaging device shown in FIG. 35.

(42) FIG. 41 is a diagram illustrating a combination of configurations which may be employed as an embodiment of a solid-state imaging device to which the present technology is applied.

(43) FIG. 42 is a schematic diagram of a cross-sectional view illustrating a configuration of a pixel portion of a solid-state imaging device to which the present technology is applied in a case of employing a four-layer structure.

(44) FIG. 43 is a block diagram illustrating a configuration example of an electronic apparatus to which the present technology is applied.

DESCRIPTION OF EMBODIMENTS

(45) Hereinafter, embodiments of the technology disclosed herein will be described with reference to the drawings.

(46) First, problems of the related art will be described.

(47) As solid-state imaging devices, there is an amplification type solid-state imaging device represented by a MOS type image sensor such as a complementary metal oxide semiconductor (CMOS). In addition, there is a charge transfer type solid-state imaging device represented by a charge coupled device (CCD).

(48) These solid-state imaging devices are frequently used in digital still cameras, digital video cameras, and the like. In recent years, as solid-state imaging devices have been mounted in mobile apparatuses such as, mobile phones and personal digital assistants (PDAs) with cameras, a MOS type image sensor has been frequently used from the viewpoint of a low power supply voltage, power consumption, and the like.

(49) The MOS type solid-state imaging device includes a pixel array (pixel region) in which a plurality of unit pixels are arranged in a two-dimensional array and a peripheral circuit region, and each of the unit pixels includes a photo diode which is a photoelectric conversion portion and a plurality of pixel transistors. A plurality of pixel transistors are formed of MOS transistors, and generally comprise three transistors including a transfer transistor, a reset transistor, an amplification transistor, or four transistors additionally including a selection transistor.

(50) In addition, in the above-described solid-state imaging device, a stacked structure has been proposed in which a plurality of semiconductor substrates having different functions are stacked in an overlapping manner and are electrically connected to each other.

(51) In the stacked structure, since each circuit can be formed optimally so as to correspond to the function of each semiconductor substrate, it is possible to easily realize high performance of a

device.

(52) For example, it is possible to manufacture a high performance solid-state imaging device by optimally forming a sensor circuit and a logical circuit so as to correspond to respective functions of a semiconductor substrate including the sensor circuit and a semiconductor substrate including the logical circuit in which a circuit processing signals is provided. At this time, through electrodes are provided in substrates of the semiconductor substrates, and thereby the plurality of semiconductor substrates are electrically connected to each other.

(53) FIG. 1 is a cross-sectional view illustrating a configuration of a pixel portion of a stacked solid-state imaging device in the related art.

(54) A solid-state imaging device related to this pixel portion includes a rear surface irradiation type CMOS image sensor which is formed by stacking a first semiconductor substrate and a second semiconductor substrate. In other words, the solid-state imaging device shown in FIG. 1 has a two-layer stacked structure.

(55) As shown in FIG. 1, an image sensor, that is, a pixel array (hereinafter, referred to as a pixel region) and a control region is formed in each region of the first semiconductor substrate 31.

(56) That is, a photodiode (PD) 34 which is a photoelectric conversion portion of each pixel is formed in each region of the semiconductor substrate (for example, a silicon substrate) 31, and a source/drain region of each pixel transistor is formed in a semiconductor well region thereof.

(57) A gate electrode is formed on a substrate surface forming the pixel via a gate insulating film, and a pixel transistor Tr1 and a pixel transistor Tr2 are formed by the gate electrode and the source/drain region corresponding thereto.

(58) The pixel transistor Tr1 adjacent to the photodiode (PD) 34 corresponds to a transfer transistor, and the source/drain region corresponds to a floating diffusion (FD).

(59) Next, an interlayer insulating film 39 of the first layer is formed on the surface of the first semiconductor substrate 31, then a connection hole is formed in the interlayer insulating film 39, and connection conductors which are connected to necessary transistors are formed therein.

(60) Successively, a metal wire of a plurality of layers (in this example, two layers) is formed via the interlayer insulating film 39 so as to be connected to each connection conductor, thereby forming a multilayer wire layer 41. The metal wire is formed of a copper (Cu) wire. Generally, each copper wire (metal wire) is covered with a barrier metal film for preventing diffusion of Cu. For this reason, a protective film which is a cap film of the copper wire is formed on the multilayer wire layer 41.

(61) The first semiconductor substrate 31 having the pixel region and the control region is formed through the steps hitherto.

(62) On the other hand, for example, a logical circuit having a signal processing circuit which controls the pixel region or controls communication with an external device and is related to signal processing is formed in each region of the second semiconductor substrate 45. In other words, a plurality of MOS transistor Tr6, MOS transistor Tr7, and MOS transistor Tr8 which form the logical circuit so as to be separated by element separation regions are formed in a p type semiconductor well region on the front surface side of the semiconductor substrate (for example, a silicon substrate) 45.

(63) Next, an interlayer insulating film 49 of the first layer is formed on the surface of the second semiconductor substrate 45, then a connection hole is formed in the interlayer insulating film 49, and connection conductors 54 which are connected to necessary transistors are formed therein.

(64) Successively, a metal wire of a plurality of layers, in this example, four layers, is formed via the interlayer insulating film 49 so as to be connected to each connection conductor 54, thereby forming a multilayer wire layer 55.

(65) The metal wire is formed of a copper (Cu) wire. A protective film which is a cap film of the copper wire (metal wire) is formed on the multilayer wire layer 55. However, the uppermost layer of the multilayer wire layer 55 is formed of an aluminum pad which may be an electrode.

(66) The second semiconductor substrate **45** having the logical circuit is formed through the steps hitherto.

(67) In addition, the first semiconductor substrate **31** and the second semiconductor substrate **45** are joined to each other such that the multilayer wire layer **41** and the multilayer wire layer **55** face each other at a bonding surface **99**. The joining is performed using, for example, plasma bonding and adhesive bonding.

(68) In addition, grinding and polishing are performed from a rear surface **31b** side of the first semiconductor substrate **31** so as to thin the first semiconductor substrate **31**, and the rear surface of the first semiconductor substrate **31** is a light incident surface in a rear surface irradiation type solid-state imaging device.

(69) Through connection holes, which penetrate through the first semiconductor substrate **31** from the rear surface side and reach the aluminum pad of the uppermost layer of the multilayer wire layer **55** of the second semiconductor substrate **45**, are formed at necessary positions of the thinned first semiconductor substrate **31**. In addition, a connection hole, which reaches the wire of the first layer of the first semiconductor substrate **31** side from the rear surface side, is formed in the first semiconductor substrate **31** around the through connection hole.

(70) Next, a through connection conductor **64** and a connection conductor **65** are embedded in the through connection holes. The through connection conductor **64** and the connection conductor **65** may use, for example, a metal such as copper (Cu) or tungsten (W).

(71) As described above, since the logical circuit performing signal processing is formed in the second semiconductor substrate **45**, it is necessary to input and output signals by connecting electrodes of the respective transistors to signal lines. That is, the logical circuit is operated based on input and output of signals with an external device. Therefore, the aluminum pad **53** of the second semiconductor substrate **45** is an electrode for external connection.

(72) For this reason, a pad hole **81** which penetrates through the first semiconductor substrate **31** is formed so as to be wire-bonded to the aluminum pad **53** of the second semiconductor substrate, thereby exposing the aluminum pad **53**.

(73) Next, an insulating protective film is formed on the entire rear surface of the first semiconductor substrate **31** such that a light blocking film **67** is formed in a region which it is necessary to block light from reaching. For example, a metal film such as tungsten may be used as the light blocking film **67**.

(74) Successively, a planarized film is formed on the light blocking film **67**, on-chip color filters **74** of, for example, red (R), green (G), and blue (B) corresponding to the respective pixels are formed on the planarized film, and an on-chip micro lens **75** is formed thereon.

(75) In addition, the pad hole **81** is formed in the first semiconductor substrate **31** so as to reach the aluminum pad **53** which is an electrode used for transmission, reception, and the like of signals with an external apparatus or circuit, from the rear surface side (light receiving surface side) of the first semiconductor substrate **31**.

(76) Thus, the process for the stacked semiconductor structure is completed. In other words, the pixel region and the control region are formed in the first semiconductor substrate **31**, and the logical circuit is formed in the second semiconductor substrate **45**.

(77) Subsequently, the stacked semiconductor structure is divided into substrates which correspond to a substrate of the rear surface irradiation type solid-state imaging device.

(78) In addition, in the solid-state imaging device with the stacked structure, it is also necessary to take into consideration the influence of noise and the like due to hot carriers. The hot carriers may be high-speed electrons having high kinetic energy that come out of a transistor and generate light when the high-speed electrons impact silicon atoms.

(79) In the solid-state imaging device with the stacked structure, transistors are provided in the second semiconductor substrate separately from the first semiconductor substrate in which the PD is provided. For this reason, light generated by hot carriers coming out of the transistors of the

second semiconductor substrate penetrates from the rear side (the opposite side to the light receiving surface) of the PD of the first semiconductor substrate, thereby causing noise.

(80) For this reason, in the solid-state imaging device with the stacked structure, in order to block light caused by the hot carriers for example, a preventative measure, such as providing a light blocking body is performed.

(81) FIG. 2 is a cross-sectional view illustrating another configuration of the pixel portion of the stacked solid-state imaging device in the related art.

(82) In the example shown in FIG. 2, a light blocking body **90** is formed under the PD **34** in the first semiconductor substrate **31**. Thus, light caused by hot carriers coming out of the MOS transistor Tr**6**, the MOS transistor Tr**7**, and the MOS transistor Tr**8** of the second semiconductor substrate **45** is blocked.

(83) Alternatively, a shape of the copper wire of the multilayer wire layer **55** may be changed, or the like, so as to block light caused by hot carriers coming out of the MOS transistor Tr**6**, the MOS transistor Tr**7**, and the MOS transistor Tr**8**.

(84) As described above with reference to FIGS. 1 and 2, in the solid-state imaging device with the two-layer stacked structure, the pad hole **81** is provided so as to be electrically connected to an external device, and light caused by the hot carriers is blocked using the light blocking body **90** or a shape of the copper wire of the multilayer wire layer **55**.

(85) A three-layer stacked solid-state imaging device has been developed. The three-layer stacked solid-state imaging device includes, for example, a third semiconductor substrate in which a memory circuit is formed in addition to the first semiconductor substrate in which the pixel region and the control region (hereinafter, referred to as a sensor circuit) and the second semiconductor substrate in which the logical circuit is formed.

(86) The three-layer stacked solid-state imaging device is manufactured, for example, as shown in FIGS. 3 and 4.

(87) First, as shown in FIG. 3, a second semiconductor substrate **112** and a third semiconductor substrate **113** are joined together such that circuit surfaces thereof face each other. In addition, interlayer films of the two semiconductor substrates are joined to each other. Further, the second semiconductor substrate **112** is thinned.

(88) Next, as shown in FIG. 4, a first semiconductor substrate **111** is joined onto the thinned second semiconductor substrate **112** in a state where the rear surface thereof face upward. In addition, interlayer films of the two semiconductor substrates are joined to each other. Further, the first semiconductor substrate **111** is thinned.

(89) As above, in a case where a stacked image sensor is formed using the three-layer stacked structure, it is necessary for the sensor circuit having a light receiving portion to incorporate light, and thus the sensor circuit is disposed in the uppermost part, and the two logical circuit and memory circuit are stacked in lower layers thereof.

(90) In addition, when the circuits are stacked, it is preferable that a support substrate for thinning a silicon substrate not be used. For this reason, in manufacturing circuits, first, the circuit surfaces of two semiconductor substrates of the lower layers are joined together so as to face each other, and the semiconductor substrate (the second semiconductor substrate **112**) of the second layer is thinned. Thereafter, the semiconductor substrate (the first semiconductor substrate **111**) of the uppermost layer is joined thereto so as to be stacked thereon as a rear surface type, and is further thinned.

(91) However, in this way, the inventors have found that the following problems occur in the three-layer stacked structure.

(92) FIG. 5 is a cross-sectional view illustrating a configuration of a pixel portion of a three-layer stacked solid-state imaging device manufactured according to FIGS. 3 and 4.

(93) A first problem in the three-layer stacked structure in FIG. 5 is that a pad hole is too deep. In FIG. 5, a pad hole **121** which is deeper than the pad hole **81** of FIG. 1 is formed.

(94) In other words, in the three-layer stacked structure, as described with reference to FIGS. 3 and 4, the circuit surface of the second semiconductor substrate **112** is joined to the circuit surface of the third semiconductor substrate so as to face each other. For this reason, an aluminum pad of the uppermost layer of the multilayer wire layer of the second semiconductor substrate is distant from the light receiving surface of the first semiconductor substrate **111**, and thus the aluminum pad **133** (an electrode for external connection) of the second semiconductor substrate is not exposed unless an opening is formed so as to penetrate through the first semiconductor substrate and, further, substantially penetrate through the second semiconductor substrate.

(95) In order to open the deep pad hole **121**, thickening of a resist is necessary. If the resist is thickened in order to open the deep pad hole **121**, curing of the resist after dry etching is problematic.

(96) For example, since an on-chip micro lens using an organic material has already been formed on the first semiconductor substrate when the opening is formed, the resist is removed using a solution, but the cured resist tends to remain in a residual state and thus impedes light incidence to the lens.

(97) In addition, in a case where the deep pad hole **121** is opened, a deposited substance occurring as a result of the dry etching is also problematic.

(98) Particularly, a deposited substance which is attached to the surface of the aluminum pad **133** or the sidewall of the pad hole **121** and is not removed, for example, absorbs humidity so as to generate fluorine ions after the three-layer stacked structure is completed, and thus causes a defect (corrosion) in which the aluminum pad metal melts.

(99) As above, in FIGS. 3 and 4, it is difficult to perform a manufacturing process of a solid-state imaging device due to the deep pad hole.

(100) A second problem in the three-layer stacked structure in FIG. 5 is that it is difficult to block light caused by hot carriers.

(101) In other words, in using the three-layer stacked structure, as described with reference to FIGS. 3 and 4, the circuit surface of the second semiconductor substrate **112** is joined to the circuit surface of the third semiconductor substrate so as to face each other. For this reason, a transistor of the second semiconductor substrate faces the first semiconductor substrate without using the multilayer wire layer. Therefore, for example, in the same manner as a case of the two-layer stacked structure, light caused by hot carriers is unable to be blocked by the copper wire of the multilayer wire layer of the second semiconductor substrate.

(102) Therefore, in the present technology, it is not necessary to provide a deep pad hole; therefore, light caused by hot carriers can be easily blocked.

(103) FIG. 6 is a cross-sectional view illustrating a configuration according to an embodiment of a pixel portion of a solid-state imaging device to which the present technology is applied. A solid-state imaging device related to this pixel portion includes a rear surface irradiation type CMOS image sensor formed by stacking a first semiconductor substrate, a second semiconductor substrate, and a third semiconductor substrate. In other words, the solid-state imaging device related to the pixel portion shown in FIG. 6 has a three-layer stacked structure.

(104) In addition, the solid-state imaging device includes, for example, a first semiconductor substrate provided with a sensor circuit, a second semiconductor substrate provided with a logical circuit, and a third semiconductor substrate provided with a memory circuit. The logical circuit and the memory circuit are respectively operated based on input and output of signals with an external device.

(105) As shown in FIG. 6, a photodiode (PD) **234** which is a photoelectric conversion portion of each pixel is formed in the semiconductor substrate (for example, a silicon substrate) **211**, and a source/drain region of each pixel transistor is formed in a semiconductor well region thereof.

(106) A gate electrode is formed on a substrate surface forming the pixel via a gate insulating film, and a pixel transistor Tr1 and a pixel transistor Tr2 are formed by the gate electrode and the

source/drain region corresponding thereto.

(107) The pixel transistor Tr1 adjacent to the photodiode (PD) **234** corresponds to a transfer transistor, and the source/drain region corresponds to a floating diffusion (FD).

(108) In addition, an interlayer insulating film is formed in the first semiconductor substrate **211**, connection hole are formed in the interlayer insulating film, and connection conductors **244** connected to the pixel transistor Tr1 and the pixel transistor Tr2 are formed therein.

(109) In addition, in order to be connected to each connection conductor **244**, a metal wire **240** of a plurality of layers is formed so as to form a multilayer wire layer **245**. The metal wire **240** is formed of a copper (Cu) wire. Generally, each copper wire is covered with a barrier metal film for preventing diffusion of Cu. For this reason, a protective film which is a cap film of the copper wire is formed on the multilayer wire layer **245**.

(110) In addition, an aluminum pad **280** which is an electrode for external connection is formed in the lowermost layer of the multilayer wire layer **245** of the first semiconductor substrate **211**. In other words, the aluminum pad **280** is formed at a position closer to an adhesive surface **291** with the second semiconductor substrate **212** than the copper wire **240**. This electrode for external connection is used as one end of a wire related to input and output of a signal with an external device. In addition, although the electrode has been described as being made of aluminum, the electrode may be made of other metals.

(111) In addition, a contact **265** which is used for electrical connection to the second semiconductor substrate **212** is formed in the first semiconductor substrate **211**. The contact **265** is connected to a contact **311** of the second semiconductor substrate **212**, described later, and is also connected to an aluminum pad **280a** of the first semiconductor substrate **211**.

(112) In addition, a pad hole **351** is formed in the first semiconductor substrate **211** so as to reach the aluminum pad **280a** from the rear surface side (the light receiving surface side) of the first semiconductor substrate **211**.

(113) FIGS. 7A and 7B are diagrams illustrating a configuration of the pad hole **351** and the aluminum pad **280a**. FIG. 7A is an enlarged view of the vicinity of the pad hole **351**, and FIG. 7B is a diagram in which the aluminum pad **280a** is viewed from the top of the pad hole **351**.

(114) As shown in FIG. 7B, a plurality of contacts **265** are arranged and are connected to an end of the aluminum pad **280a** so as to reduce contact resistance.

(115) Returning to FIG. 6, in the same manner as the case described with reference to FIG. 1, an insulating protective film is formed on the entire rear surface in the first semiconductor substrate **211** so as to form a light block film in a region which it is necessary to block light from reaching. Further, on-chip color filters **274** which correspond to the respective pixels are formed on the planarized film, and an on-chip micro lens **275** is formed thereon.

(116) Meanwhile, a logical circuit is formed in the second semiconductor substrate **212**. In other words, a MOS transistor Tr6, a MOS transistor Tr7, and a MOS transistor Tr8 which comprise a plurality of transistors forming the logical circuit, are formed in a p type semiconductor well region of the semiconductor substrate (for example, a silicon substrate) **212**.

(117) In addition, connection conductors **254** which are connected to the MOS transistor Tr6, the MOS transistor Tr7, and the MOS transistor Tr8 are formed in the second semiconductor substrate **212**.

(118) In addition, a metal wire **250** of a plurality of layers is formed, and a multilayer wire layer **255** is formed so as to be connected to the respective connection conductors **254**.

(119) The metal wire is formed of a copper (Cu) wire. A protective film which is a cap film of the copper wire (metal wire) **250** is formed on the multilayer wire layer **255**.

(120) In addition, an aluminum pad **320** which is an electrode is formed in the lowermost layer of the multilayer wire layer **255** of the second semiconductor substrate **212**.

(121) Further, a contact **311** which is used for electrical connection to the first semiconductor substrate **211** and the third semiconductor substrate **213** is formed in the second semiconductor

substrate **212**. The contact **311** is connected to the contact **265** of the first semiconductor substrate **211** and is also connected to an aluminum pad **330a** of the third semiconductor substrate **213**.

(122) In addition, a memory circuit is formed in the third semiconductor substrate **213**. In other words, a MOS transistor Tr**11**, a MOS transistor Tr**12**, and a MOS transistor Tr**13** which are a plurality of transistors forming the memory circuit are formed in a p type semiconductor well region of the semiconductor substrate (for example, a silicon substrate) **213**.

(123) In addition, connection conductors **344** which are connected to the MOS transistor Tr**11**, the MOS transistor Tr**12**, and the MOS transistor Tr**13** are formed in the third semiconductor substrate **213**.

(124) In addition, a metal wire **340** of a plurality of layers is formed, and a multilayer wire layer **345** is formed so as to be connected to the respective connection conductors **344**.

(125) The metal wire is formed of a copper (Cu) wire. A protective film which is a cap film of the copper wire (metal wire) **340** is formed on the multilayer wire layer **345**.

(126) In addition, an aluminum pad **330** which is an electrode is formed in the uppermost layer of the multilayer wire layer **345**.

(127) In the solid-state imaging device shown in FIG. **6**, the contact **265** and the contact **311** are provided, and thus input and output of signals can be performed between the first semiconductor substrate **211** to the third semiconductor substrate **213** via the aluminum pad **280a**.

(128) Also in the solid-state imaging device shown in FIG. **6**, as described with reference to FIGS. **3** and **4**, interlayer films of the second semiconductor substrate **212** and the third semiconductor substrate **213** are joined to each other at an adhesive surface **292**. In addition, the interlayer films of the second semiconductor substrate **212** and the first semiconductor substrate **211** are joined to each other at the adhesive surface **291**.

(129) In other words, as described with reference to FIGS. **3** and **4**, first, the two semiconductor substrates of the lower layers are joined together such that the circuit surfaces thereof face each other, and the semiconductor substrate (the second semiconductor substrate **212**) of the second layer is thinned. Next, the semiconductor substrate (the first semiconductor substrate **211**) of the uppermost layer is joined thereto so as to be stacked thereon as a rear surface type, and is further thinned. At this time, after the upper layer of the contact **311** is planarized, the first semiconductor substrate **211** is joined to the second semiconductor substrate **212** as a rear surface type.

(130) In this way, when the circuits are stacked, a support substrate for thinning the silicon substrate is not used.

(131) In the present technology, the aluminum pad **280** is also provided in the first semiconductor substrate **211**. In addition, an electrode for an external electrode is not provided in the second semiconductor substrate **212** having the logical circuit in which input and output of signals to and from an external device are necessary, or the third semiconductor substrate **213** having the memory circuit, and an electrode (the aluminum pad **280a**) for an external connection is provided in the first semiconductor substrate **211** having the sensor circuit.

(132) In this way, it is possible to expose the electrode for external connection without deepening the pad hole **351**.

(133) In addition, in the present technology, since the aluminum pad **280** is also provided in the first semiconductor substrate **211**, it is possible to block light caused by hot carriers coming out of each transistor of the second semiconductor substrate **212** by the aluminum pad **280**.

(134) As above, in the present technology, it is not necessary to provide a deep pad hole, and it is possible to easily prevent the influence of noise and the like due to hot carriers by blocking the light caused by hot carriers.

(135) In addition, and with respect to FIG. **6**, although the aluminum pad **320** is provided in the second semiconductor substrate and the aluminum pad **330** is provided in the third semiconductor substrate **213**, the aluminum pad **320** and the aluminum pad **330** may not be provided. For example, if the contact **311** is to be directly connected to the copper wire **340** of the third

semiconductor substrate **213**, it is unnecessary to provide the aluminum pad **320** and the aluminum pad **330**.

(136) In addition, a shape of the contact which electrically connects the semiconductor substrates to each other is not limited to the shapes of the contact **265** and the contact **311**. In addition, since a hole for forming a contact can be formed before an on-chip micro lens is formed, even the problem associated with a deep pad hole is not an issue. For example, a contact may be provided which penetrates through the second semiconductor substrate so as to connect the copper wire of the first semiconductor substrate to the copper wire of the third semiconductor substrate.

(137) Alternatively, a light blocking body which blocks light caused by hot carriers may be formed.

(138) FIG. **8** is a cross-sectional view illustrating a configuration according to another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied. In the same manner as in FIG. **6**, a solid-state imaging device related to this pixel portion includes a rear surface type CMOS image sensor formed by stacking a first semiconductor substrate, a second semiconductor substrate, and a third semiconductor substrate. In other words, the solid-state imaging device related to the pixel portion shown in FIG. **8** also has a three-layer stacked structure.

(139) In the example shown in FIG. **8**, a light blocking body **360** is disposed in an interlayer film which is the uppermost layer of the second semiconductor substrate **212** in FIG. **8**. Thus, it is possible to more reliably block light caused by hot carriers coming out of each transistor of the second semiconductor substrate **212**.

(140) In addition, since the aluminum pad **280** is formed in the first semiconductor substrate **211**, the light blocking body **360** is not disposed in the first semiconductor substrate **211** and is disposed in the interlayer film of the second semiconductor substrate **212**.

(141) The other constituent elements in FIG. **8** are the same as in the case described with reference to FIG. **6**, and thus detailed description thereof will be omitted.

(142) Alternatively, a copper wire may be formed in the interlayer film which is the uppermost layer of the second semiconductor substrate **212** in FIG. **8**, and light caused by hot carriers may be blocked by a combination of the aluminum pad and the copper wire.

(143) FIG. **9** is a cross-sectional view illustrating a configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied. In the same manner as in FIG. **6**, a solid-state imaging device related to this pixel portion includes a rear surface irradiation type CMOS image sensor formed by stacking a first semiconductor substrate, a second semiconductor substrate, and a third semiconductor substrate. In other words, the solid-state imaging device related to the pixel portion shown in FIG. **9** also has a three-layer stacked structure.

(144) In the example shown in FIG. **9**, a copper wire **370** is disposed in an interlayer film which is the uppermost layer of the second semiconductor substrate **212** in FIG. **9**.

(145) A part of the contact **311** is formed in the interlayer film which is the uppermost layer of the second semiconductor substrate **212** in FIG. **9**. For example, if the copper wire **370** is further formed in the interlayer film when the contact **311** is formed, a solid-state imaging device with the configuration shown in FIG. **9** can be obtained.

(146) When light is blocked by a combination of the copper wire **370** and the aluminum pad **280**, it is possible to more reliably block light caused by hot carriers coming out of each transistor of the second semiconductor substrate **212**. In addition, in an embodiment of the configuration shown in FIG. **9**, additional freedom in designing wires related to the aluminum pad **280** may be utilized, as compared with a case of blocking light only by the aluminum pad **280**, for example, as shown in FIG. **6**.

(147) The other constituent elements in FIG. **9** are the same as in the case described with reference to FIG. **6**, and thus detailed description thereof will be omitted.

(148) FIG. **10** is a diagram illustrating a schematic configuration of a solid-state imaging device to which the present technology is applied. This solid-state imaging device **401** includes, for example,

a CMOS image sensor.

(149) The solid-state imaging device **401** of FIG. **10** includes a pixel region (a so-called pixel array) **403** in which pixels **402** including a plurality of photoelectric conversion portions are regularly arranged in a two-dimensional array on the semiconductor substrate **411** and a peripheral circuit portion.

(150) Each of the pixels **402** includes, for example, a photodiode which is the photoelectric conversion portion and a plurality of pixel transistors (so-called MOS transistors).

(151) In addition, the pixels **402** may have a shared pixel structure. This pixel shared structure is formed by a plurality of photodiodes, a plurality of transfer transistors, a single shared floating diffusion, and another shared transistor.

(152) The peripheral circuit portion includes a vertical driving circuit **404**, a column signal processing circuit **405**, a horizontal driving circuit **406**, an output circuit **407**, a control circuit **408**, and the like.

(153) The control circuit **408** receives an input clock and data for commanding an operation mode and the like, and outputs data such as internal information of the solid-state imaging device. In other words, the control circuit **408** generates a clock signal used as a reference of operations of the vertical driving circuit **404**, the column signal processing circuit **405**, the horizontal driving circuit **406**, and the like, and control signals on the basis of a vertical synchronization signal, a horizontal synchronization signal, and a master clock. In addition, these signals are input to the vertical driving circuit **404**, the column signal processing circuit **405**, the horizontal driving circuit **406**, and the like.

(154) The vertical driving circuit **404** including, for example, shift registers, selects a pixel driving line, and supplies a pulse for driving the pixels to the selected pixel driving line so as to drive the pixels in the unit of a row. In other words, the vertical driving circuit **404** sequentially selectively scans the respective pixels **402** of the pixel region **403** in the vertical direction in the unit of a row, and supplies a pixel signal based on signal charge which is generated according to a light receiving amount in, for example, the photodiode which is a photoelectric conversion portion of each pixel **402**, to the column signal processing circuit **405** via a vertical signal line **409**.

(155) The column signal processing circuit **405** is disposed, for example, for each column of the pixels **402**, and performs a signal process such as noise removal on signals output from the pixels **402** of one row for each pixel column. In other words, the column signal processing circuit **405** performs signal processes such as CDS for removing fixed pattern noise unique to the pixels **402**, signal amplification, and AD conversion. In an output end of the column signal processing circuit **405**, a horizontal selection switch (not shown) is provided so as to be connected to a horizontal signal line **410**.

(156) The horizontal driving circuit **406** includes, for example, shift registers, sequentially outputs horizontal scanning pulses so as to sequentially select the respective column signal processing circuits **405**, thereby outputting a pixel signal from each of the column signal processing circuits **405** to the horizontal signal line **410**.

(157) The output circuit **407** performs a signal process on the signals which are sequentially supplied from the respective column signal processing circuits **405** via the horizontal signal line **410** so as to be output. For example, only buffering may be performed, or black level adjustment, column disparity correction, a variety of digital signal processes, and the like may be performed. An input and output terminal **412** sends and receives signals to and from an external device.

(158) The solid-state imaging device **401** shown in FIG. **10** includes a rear surface irradiation type CMOS image sensor with a three-layer stacked structure. For example, the pixels **402** shown in FIG. **10** are sensor circuits formed in the first semiconductor substrate, and the peripheral circuits are logical circuits formed in the second semiconductor substrate or memory circuits formed in the third semiconductor substrate.

(159) In the above-described embodiment, and as previously described, the aluminum pad **280** is

formed in the lowermost layer of the multilayer wire layer **245** of the first semiconductor substrate **211**. However, for example, in a case where the aluminum pad **280** is disposed in the first semiconductor substrate **211**, it is necessary to provide an electro-static discharge (ESD) circuit which is a circuit for protecting circuits of the first semiconductor substrate **211** from overcurrent, and this increases the number of steps.

(160) In addition, in the above example described with reference to FIG. **6**, it is possible to achieve an effect in which light caused by hot carriers is blocked by the aluminum pad **280** disposed in the first semiconductor substrate **211**. However, since the multilayer wire layer **245** of the first semiconductor substrate **211** includes three wire layers, it is difficult to dispose the aluminum pad **280** so as to block light caused by hot carriers without restricting a shape of the copper wire **240**.

(161) For example, since the multilayer wire layer **255** of the second semiconductor substrate **212** includes six wire layers, if the aluminum pad **280** is disposed in the second semiconductor substrate **212**, it is easy to dispose the aluminum pad **280** so as to block light caused by hot carriers without restricting a shape of the metal wire **250**.

(162) In addition, in the above-described embodiment, the contact **265** used for electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212** has a configuration in which conductors embedded in two through holes which penetrate through the first semiconductor substrate **211** in the vertical direction are connected to each other on the light receiving surface (the uppermost surface in FIG. **9**) of the first semiconductor substrate **211**. This contact is also referred to as a twin contact. The contact **311** used for electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213** is also a twin contact.

(163) However, since it is necessary to provide two through holes for the twin contact, the number of manufacturing steps increases, and the area occupying the substrate also increases.

(164) For example, when a contact is formed which penetrates through the first semiconductor substrate **211** from the uppermost side of the first semiconductor substrate **211** in FIG. **9** and reaches the wire inside the multilayer wire layer **255** of the second semiconductor substrate, a part of which reaches the wire inside the multilayer wire layer **245** of the first semiconductor substrate **211**, only a single through hole is provided and thereby the first semiconductor substrate **211** can be electrically connected to the second semiconductor substrate **212**. This contact is also referred to as a shared contact.

(165) When the shared contact is used for electrical connection between the semiconductor substrates, manufacturing steps can be simplified and thus the area occupying the substrate can be reduced as compared with a case of using the twin contact.

(166) In addition, when semiconductor substrates are joined together, a method in which the copper wires of the multilayer wire layers are directly bonded to each other has been utilized. If the copper wires of the multilayer wire layers are directly bonded to each other, it is unnecessary to provide a contact for electrical connection between semiconductor substrates, manufacturing steps can be further simplified, and thus the area occupying the substrate can be reduced. In addition, the method of directly bonding the copper wires to each other is also referred to as direct bonding.

(167) FIG. **11** is a schematic diagram of the cross-sectional view related to the configuration of the pixel portion of the solid-state imaging device shown in FIG. **6**. As shown in FIG. **11**, the pad hole **351** is formed in the first semiconductor substrate **211** so as to reach the aluminum pad **280a** from the rear surface side (light receiving surface side) of the first semiconductor substrate **211**. In addition, the aluminum pad **280** is formed in the multilayer wire layer **245** of the first semiconductor substrate **211**.

(168) Further, in the configuration shown in FIG. **11**, the multilayer wire layer **255** of the second semiconductor substrate faces the third semiconductor substrate **213** side (the lower side of FIG. **11**), and the first semiconductor substrate **211** is joined to the second semiconductor substrate **212**.

(169) In addition, in the configuration shown in FIG. **11**, the contact **265** used for electrical

connection between the first semiconductor substrate **211** and the second semiconductor substrate **212** and the contact **311** used for electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213** are provided. The contact **265** and the contact **311** are respectively formed by a twin contact.

(170) FIG. **12** is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(171) In the configuration shown in FIG. **12**, unlike in the case of FIG. **11**, the multilayer wire layer **255** of the second semiconductor substrate faces the first semiconductor substrate **211** side (the upper side in FIG. **12**), and the first semiconductor substrate **211** is joined to the second semiconductor substrate **212**.

(172) In addition, in the configuration shown in FIG. **12**, unlike in the case of FIG. **11**, the aluminum pad **280** is provided in the multilayer wire layer **255** of the second semiconductor substrate **212**. Further, the pad hole **351** is formed in the first semiconductor substrate **211** so as to reach the aluminum pad **280a** from the rear surface side (light receiving surface side) of the first semiconductor substrate **211**.

(173) As shown in FIG. **12**, the multilayer wire layer **255** of the second semiconductor substrate **212** faces the first semiconductor substrate side, and thus light caused by hot carriers can be blocked by the multilayer wire layer **255**. In addition, the aluminum pad **280** is disposed in the multilayer wire layer **255** including the six wire layers, and thus it is easy to dispose the aluminum pad **280** so as to block light caused by hot carriers without restricting a shape of the metal wire **250**.

(174) In addition, since the aluminum pad **280** is provided in the multilayer wire layer **255** of the second semiconductor substrate **212**, it is unnecessary to provide an ESD circuit in the first semiconductor substrate **211** (because an ESD circuit is preferably formed in the second semiconductor substrate), and thus it is possible to manufacture a solid-state imaging device at a low cost.

(175) In addition, in the configuration shown in FIG. **12**, the contact **266** used for electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212** and the contact **312** used for electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213** are provided. The contact **266** and the contact **312** are respectively formed by a twin contact.

(176) In a case of the configuration shown in FIG. **12**, unlike in the case of FIG. **11**, the contact **312** penetrates through the first semiconductor substrate **211** and the second semiconductor substrate **212** and reaches the multilayer wire layer **345** of the third semiconductor substrate **213**.

(177) Next, a manufacturing process of the solid-state imaging device shown in FIG. **12** will be described.

(178) First, as shown in FIG. **13**, the first semiconductor substrate **211**, the second semiconductor substrate **212**, and the third semiconductor substrate **213** are prepared which are respectively provided with the multilayer wire layers. As shown in FIG. **13**, the first semiconductor substrate **211** is provided with the multilayer wire layer **245**, the second semiconductor substrate **212** is provided with the multilayer wire layer **255**, and the third semiconductor substrate **213** is provided with the multilayer wire layer **345**.

(179) In addition, as shown in FIG. **13**, the aluminum pad **280** is formed in the multilayer wire layer **255** of the second semiconductor substrate **212**.

(180) Next, as shown in FIG. **14**, the first semiconductor substrate **211** is joined to the second semiconductor substrate **212**. At this time, the first semiconductor substrate **211** is joined to the second semiconductor substrate **212** such that the multilayer wire layer **245** and the multilayer wire layer **255** face each other.

(181) In addition, as shown in FIG. **15**, the second semiconductor substrate **212** is thinned. In FIG. **15**, the width of the second semiconductor substrate **212** in the vertical direction of FIG. **15** is

reduced.

(182) Next, as shown in FIG. 16, the third semiconductor substrate **213** is joined to the second semiconductor substrate **212**. At this time, the second semiconductor substrate **212** is joined to the third semiconductor substrate **213** such that the multilayer wire layer **345** of the third semiconductor substrate faces upward in FIG. 16.

(183) In addition, as shown in FIG. 17, the first semiconductor substrate **211** is thinned. In FIG. 17, the width of the first semiconductor substrate **211** in the vertical direction of FIG. 17 is reduced.

(184) Next, as shown in FIG. 18, the contact **312** and the contact **266** are formed. At this time, a hole is provided which reaches the multilayer wire layer **245** from the light receiving surface of the first semiconductor substrate **211**, and a hole is provided which reaches the aluminum pad **280** of the multilayer wire layer **255** from the light receiving surface, thereby forming the contact **266**. In addition, a hole is provided which reaches the aluminum pad **280** of the multilayer wire layer **255** from the light receiving surface of the first semiconductor substrate **211**, and a hole is provided which reaches the multilayer wire layer **345** from the light receiving surface, thereby forming the contact **312**.

(185) In addition, as shown in FIG. 19, the pad hole **351** is formed so as to reach the aluminum pad **280a** from the rear surface side (light receiving surface side) of the first semiconductor substrate **211**.

(186) In this way, the solid-state imaging device described with reference to FIG. 12 is manufactured. Thus, it is possible to block light caused by hot carriers by the multilayer wire layer **255**. In addition, the aluminum pad **280** is disposed in the multilayer wire layer **255** including the six wire layers, and thus it is easy to locate the aluminum pad **280** so as to block light caused by hot carriers without restricting a shape of the metal wire **250**. Further, since the aluminum pad **280** is provided in the multilayer wire layer **255** of the second semiconductor substrate **212**, it is unnecessary to provide an ESD circuit in the first semiconductor substrate **211** (because an ESD circuit is preferably formed in the second semiconductor substrate), and thus it is possible to manufacture a solid-state imaging device at a low cost.

(187) FIG. 20 is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(188) In the configuration shown in FIG. 20, in the same manner as in the case of FIG. 11, the multilayer wire layer **255** of the second semiconductor substrate faces the third semiconductor substrate **213** side (the lower side of FIG. 20), and the first semiconductor substrate **211** is joined to the second semiconductor substrate **212**.

(189) In addition, in the configuration shown in FIG. 20, in the same manner as in the case of FIG. 11, the contact **265** used for electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212** and the contact **311** used for electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213** are provided. The contact **265** and the contact **311** are respectively formed by a twin contact.

(190) In addition, in the configuration shown in FIG. 20, unlike in the case of FIG. 11, an insulating film layer **230** is formed between the first semiconductor substrate **211** and the second semiconductor substrate **212**. Further, the aluminum pad **280a** is disposed in the insulating film layer **230**, and the aluminum pad **280a** is connected to a contact **313** which is connected to the multilayer wire layer **255** of the second semiconductor substrate **212**.

(191) Furthermore, in the configuration shown in FIG. 20, the pad hole **351** is formed in the first semiconductor substrate **211** so as to reach the aluminum pad **280a** inside the insulating film layer **230** from the rear surface side (light receiving surface side) of the first semiconductor substrate **211**.

(192) In a case of the configuration shown in FIG. 20, since the aluminum pad **280** is provided in the insulating film layer **230**, it is unnecessary to provide an ESD circuit in the first semiconductor

substrate **211** (because an ESD circuit is preferably formed in the second semiconductor substrate), and thus it is possible to manufacture a solid-state imaging device at a low cost.

(193) Next, a manufacturing process of the solid-state imaging device shown in FIG. **20** will be described.

(194) First, as shown in FIG. **21**, the first semiconductor substrate **211**, the second semiconductor substrate **212**, and the third semiconductor substrate **213** are prepared which are respectively provided with the multilayer wire layers. As shown in FIG. **21**, the first semiconductor substrate **211** is provided with the multilayer wire layer **245**, the second semiconductor substrate **212** is provided with the multilayer wire layer **255**, and the third semiconductor substrate **213** is provided with the multilayer wire layer **345**.

(195) In addition, as shown in FIG. **21**, the aluminum pad **280** is not formed in the multilayer wire layer **255** of the second semiconductor substrate **212**.

(196) Next, as shown in FIG. **22**, the second semiconductor substrate **212** is joined to the third semiconductor substrate **213**. At this time, the second semiconductor substrate **212** is joined to the third semiconductor substrate **213** such that the multilayer wire layer **255** and the multilayer wire layer **345** face each other.

(197) In addition, as shown in FIG. **23**, the second semiconductor substrate **212** is thinned. In FIG. **23**, the width of the second semiconductor substrate **212** in the vertical direction of FIG. **23** is reduced.

(198) Next, as shown in FIG. **24**, the contact **311** and the contact **313** are formed. At this time, a hole is provided which reaches the multilayer wire layer **345** from the upper surface of the second semiconductor substrate **212** in FIG. **24**, and a hole is provided which reaches the multilayer wire layer **255** from the upper surface of the second semiconductor substrate **212** in FIG. **24**, thereby forming the contact **311**. In addition, a hole is provided which reaches the multilayer wire layer **255** from the upper surface of the second semiconductor substrate **212** in FIG. **24**, thereby forming the contact **313**.

(199) In addition, as shown in FIG. **25**, the aluminum pad **280a** is formed, and the insulating film layer **230** is formed. As shown in FIG. **25**, the aluminum pad **280a** is formed so as to be connected to the upper end of the contact **313** in FIG. **25**. In addition, the insulating film layer **230** is formed around the aluminum pad **280a** in the upper surface of the second semiconductor substrate **212** in FIG. **25**.

(200) Next, as shown in FIG. **26**, the first semiconductor substrate **211** is joined to the second semiconductor substrate **212** (more accurately, the insulating film layer **230**). At this time, the first semiconductor substrate **211** is joined to the second semiconductor substrate **212** such that the multilayer wire layer **245** comes into contact with the insulating film layer **230**.

(201) In addition, the first semiconductor substrate **211** is thinned. In FIG. **26**, the width of the first semiconductor substrate **211** in the vertical direction of FIG. **26** is reduced.

(202) In addition, as shown in FIG. **27**, the pad hole **351** is formed so as to reach the aluminum pad **280a** from the rear surface side (light receiving surface side) of the first semiconductor substrate **211**. Successively, a hole is provided which reaches the multilayer wire layer **245** from the light receiving surface of the first semiconductor substrate **211**, and a hole is provided which reaches the contact **311** from the light receiving surface, thereby forming the contact **265**.

(203) In this way, the solid-state imaging device described with reference to FIG. **20** is manufactured. Further, since the aluminum pad **280** is provided in the insulating film layer **230**, it is unnecessary to provide an ESD circuit in the first semiconductor substrate **211** (because an ESD circuit is preferably formed in the second semiconductor substrate), and thus it is possible to manufacture a solid-state imaging device at a low cost.

(204) FIG. **28** is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(205) In the configuration shown in FIG. 28, in the same manner as in the case of FIG. 11, the pad hole 351 is formed in the first semiconductor substrate 211 so as to reach the aluminum pad 280a from the rear surface side (light receiving surface side) of the first semiconductor substrate 211. In addition, the aluminum pad 280 is formed in the multilayer wire layer 245 of the first semiconductor substrate 211.

(206) In the configuration shown in FIG. 28, in the same manner as in the case of FIG. 11, the multilayer wire layer 255 of the second semiconductor substrate faces the third semiconductor substrate 213 side (the lower side of FIG. 28), and the first semiconductor substrate 211 is joined to the second semiconductor substrate 212.

(207) In addition, in the configuration shown in FIG. 28, in the same manner as in the case of FIG. 11, the contact 265 used for electrical connection between the first semiconductor substrate 211 and the second semiconductor substrate 212 is provided. The contact 265 is formed by a twin contact.

(208) In the configuration shown in FIG. 28, unlike in the case of FIG. 11, the contact 311 used for electrical connection between the second semiconductor substrate 212 and the third semiconductor substrate 213 is not provided. On the other hand, the contact 314 and the contact 315 used for electrical connection between the second semiconductor substrate 212 and the third semiconductor substrate 213 are provided.

(209) Each of the contact 314 and the contact 315 is formed by providing a through hole which penetrates through the second semiconductor substrate 212 and reaches the multilayer wire layer 345 of the third semiconductor substrate 213 and embedding a conductor therein. In other words, each of the contact 314 and the contact 315 connects the multilayer wire layer 255 of the second semiconductor substrate 212 to the multilayer wire layer 345 of the third semiconductor substrate 213 by providing only a single through hole.

(210) In other words, each of the contact 314 and the contact 315 is formed by a shared contact.

(211) In the configuration shown in FIG. 28, it is possible to simplify manufacturing steps and to reduce the area occupying the substrate by using the shared contact.

(212) Although the description has been provided here of a case where the shared contact is used for electrical connection between the second semiconductor substrate 212 and the third semiconductor substrate 213, the shared contact may be used for electrical connection between the first semiconductor substrate 211 and the second semiconductor substrate 212.

(213) In addition, similarly, in the solid-state imaging device with the configuration described with reference to FIG. 11, 12 or 20, the shared contact may also be used for electrical connection between the first semiconductor substrate 211 and the second semiconductor substrate 212, or electrical connection between the second semiconductor substrate 212 and the third semiconductor substrate 213.

(214) In other words, in the configuration (FIG. 11) in which the aluminum pad 280 is provided in the multilayer wire layer 245 of the first semiconductor substrate 211, the shared contact may be used for electrical connections between the respective semiconductor substrates. In addition, in the configuration (FIG. 12) in which the aluminum pad 280 is provided in the multilayer wire layer 255 of the second semiconductor substrate 212, the shared contact may be used for electrical connections between the respective semiconductor substrates. Further, in the configuration (FIG. 20) in which the aluminum pad 280 is provided in the insulating film layer 230, the shared contact may be used for electrical connections between the respective semiconductor substrates.

(215) FIG. 29 is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(216) In the configuration shown in FIG. 29, in the same manner as in the case of FIG. 11, the pad hole 351 is formed in the first semiconductor substrate 211 so as to reach the aluminum pad 280a from the rear surface side (light receiving surface side) of the first semiconductor substrate 211. In addition, the aluminum pad 280 is formed in the multilayer wire layer 245 of the first

semiconductor substrate **211**.

(217) In the configuration shown in FIG. **29**, in the same manner as in the case of FIG. **11**, the multilayer wire layer **255** of the second semiconductor substrate faces the third semiconductor substrate **213** side (the lower side of FIG. **29**), and the first semiconductor substrate **211** is joined to the second semiconductor substrate **212**.

(218) In addition, in the configuration shown in FIG. **29**, a contact **267** used for an electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213** is provided. The contact **267** is formed by a twin contact.

(219) Further, in the configuration shown in FIG. **29**, a metal wire **250a** in the multilayer wire layer **255** of the second semiconductor substrate **212** is directly bonded to a metal wire **340a** in the multilayer wire layer **345** of the third semiconductor substrate **213**. Furthermore, a metal wire **250b** in the multilayer wire layer **255** is directly bonded to a metal wire **340b** in the multilayer wire layer **345**. Thus, the second semiconductor substrate **212** is electrically connected to the third semiconductor substrate **213**.

(220) In other words, in a case of the configuration shown in FIG. **29**, not a contact but direct bonding is used for electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213**. Therefore, it is possible to simplify manufacturing steps and to reduce the area occupying the substrate.

(221) In addition, the direct bonding is disclosed in detail in, for example, Japanese Unexamined Patent Application Publication No. 2013-033900 which is hereby incorporated herein by reference in its entirety for all that it teaches and for all purposes.

(222) Next, a manufacturing process of the solid-state imaging device shown in FIG. **29** will be described.

(223) First, as shown in FIG. **30**, the first semiconductor substrate **211**, the second semiconductor substrate **212**, and the third semiconductor substrate **213** are prepared which are respectively provided with the multilayer wire layers. As shown in FIG. **30**, the first semiconductor substrate **211** is provided with the multilayer wire layer **245**, the second semiconductor substrate **212** is provided with the multilayer wire layer **255**, and the third semiconductor substrate **213** is provided with the multilayer wire layer **345**.

(224) In addition, as shown in FIG. **30**, the aluminum pad **280** is formed in the multilayer wire layer **245** of the first semiconductor substrate **211**. Further, the metal wire **250** and the metal wire **250b** are formed in the multilayer wire layer **255** of the second semiconductor substrate, and the metal wire **340a** and the metal wire **340b** are formed in the multilayer wire layer **345** of the third semiconductor substrate.

(225) Next, as shown in FIG. **31**, the second semiconductor substrate **212** is joined to the third semiconductor substrate **213**. At this time, the second semiconductor substrate **212** is joined to the third semiconductor substrate **213** such that the multilayer wire layer **255** and the multilayer wire layer **345** face each other. In addition, the metal wire **250a** is directly bonded to the metal wire **340a**, and the metal wire **250b** is directly bonded to the metal wire **340b**.

(226) In addition, the second semiconductor substrate **212** is thinned. In FIG. **31**, the width of the second semiconductor substrate **212** in the vertical direction of FIG. **31** is reduced.

(227) Next, as shown in FIG. **32**, the first semiconductor substrate **211** is joined to the second semiconductor substrate **212**. At this time, the multilayer wire layer **255** of the second semiconductor substrate faces the third semiconductor substrate **213** side (the lower side of FIG. **32**), and the first semiconductor substrate **211** is joined to the second semiconductor substrate **212**.

(228) In addition, the first semiconductor substrate **211** is thinned. In FIG. **32**, the width of the first semiconductor substrate **211** in the vertical direction of FIG. **32** is reduced.

(229) Next, the contact **267** is formed as shown in FIG. **33**. At this time, a hole is provided which reaches the multilayer wire layer **245** from the light receiving surface of the first semiconductor substrate **211**, and a hole is provided which reaches the multilayer wire layer **255** from the light

receiving surface, thereby forming the contact **267**.

(230) In addition, as shown in FIG. **34**, the pad hole **351** is formed so as to reach the aluminum pad **280a** from the rear surface side (light receiving surface side) of the first semiconductor substrate **211**.

(231) In this way, the solid-state imaging device described with reference to FIG. **29** is manufactured. Since not a contact but direction bonding is used for electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213**, it is possible to simplify manufacturing steps and to reduce the area occupying the substrate.

(232) Although the description has been provided here of a case where the direct bonding is used as an electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213**, the direct bonding may be used as an electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212**.

(233) Similarly, in the solid-state imaging device with the configuration described with reference to FIG. **11**, **12** or **20**, the direct bonding may also be used as an electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212**, or as an electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213**.

(234) In other words, in the configuration (FIG. **11**) in which the aluminum pad **280** is provided in the multilayer wire layer **245** of the first semiconductor substrate **211**, the direct bonding may be used as an electrical connection between the respective semiconductor substrates. In addition, in the configuration (FIG. **12**) in which the aluminum pad **280** is provided in the multilayer wire layer **255** of the second semiconductor substrate **212**, the direct bonding may be used as an electrical connection between the respective semiconductor substrates. Further, in the configuration (FIG. **20**) in which the aluminum pad **280** is provided in the insulating film layer **230**, the direct bonding may be used as an electrical connection between the respective semiconductor substrates.

(235) FIG. **35** is a schematic diagram of the cross-sectional view illustrating the configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(236) In the configuration shown in FIG. **35**, unlike in the case of FIG. **29**, a contact **268** and a contact **316** used as an electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212** are provided. In other words, in a case of the configuration shown in FIG. **35**, the lower left end of the contact **268** in FIG. **35** is connected to the upper end of the contact **316** in FIG. **35**, and thereby the first semiconductor substrate **211** is electrically connected to the second semiconductor substrate **212**. In addition, the contact **268** is formed by a twin contact.

(237) In the configuration shown in FIG. **35**, it is unnecessary to provide a hole which reaches the multilayer wire layer **255** from the light receiving surface, for example, unlike in forming the contact **267** of FIG. **29**. For this reason, it is possible to more simply form a contact.

(238) A configuration of the other elements in FIG. **35** is the same as in the case of FIG. **29**, and detailed description thereof will be made.

(239) Next, a manufacturing process of the solid-state imaging device shown in FIG. **35** will be described.

(240) First, as shown in FIG. **36**, the first semiconductor substrate **211**, the second semiconductor substrate **212**, and the third semiconductor substrate **213** are prepared which are respectively provided with the multilayer wire layers. As shown in FIG. **36**, the first semiconductor substrate **211** is provided with the multilayer wire layer **245**, the second semiconductor substrate **212** is provided with the multilayer wire layer **255**, and the third semiconductor substrate **213** is provided with the multilayer wire layer **345**.

(241) In addition, as shown in FIG. **36**, the aluminum pad **280** is formed in the multilayer wire layer **245** of the first semiconductor substrate **211**. Further, the metal wire **250a** and the metal wire

250b are formed in the multilayer wire layer **255** of the second semiconductor substrate, and the metal wire **340a** and the metal wire **340b** are formed in the multilayer wire layer **345** of the third semiconductor substrate.

(242) Next, as shown in FIG. **37**, the second semiconductor substrate **212** is joined to the third semiconductor substrate **213**. At this time, the second semiconductor substrate **212** is joined to the third semiconductor substrate **213** such that the multilayer wire layer **255** and the multilayer wire layer **345** face each other. In addition, the metal wire **250a** is directly bonded to the metal wire **340a**, and the metal wire **250b** is directly bonded to the metal wire **340b**.

(243) In addition, the second semiconductor substrate **212** is thinned. In FIG. **37**, the width of the second semiconductor substrate **212** in the vertical direction of FIG. **31** is reduced.

(244) In addition, as shown in FIG. **38**, the contact **316** is formed. At this time, a hole is provided which reaches the multilayer wire layer **255** from the upper surface of the second semiconductor substrate **212** in FIG. **38** so as to form the contact **316**.

(245) Next, as shown in FIG. **39**, the first semiconductor substrate **211** is joined to the second semiconductor substrate **212**. At this time, the first semiconductor substrate **211** is joined to the second semiconductor substrate **212** such that the rear surface of the first semiconductor substrate **211** becomes a light receiving surface.

(246) In addition, the first semiconductor substrate **211** is thinned. In FIG. **39**, the width of the first semiconductor substrate **211** in the vertical direction of FIG. **39** is reduced.

(247) Further, a hole is provided which reaches the upper surface of the second semiconductor substrate in FIG. **39** from the light receiving surface of the first semiconductor substrate **211**, and a hole is provided which reaches the aluminum pad **280** of the multilayer wire layer **245** from the light receiving surface, thereby forming the contact **268**.

(248) In addition, as shown in FIG. **40**, the pad hole **351** is formed so as to reach the aluminum pad **280a** from the light receiving surface of the first semiconductor substrate **211**.

(249) In this way, the solid-state imaging device described with reference to FIG. **35** is manufactured. In the configuration shown in FIG. **35**, as described above, the contact **268** and the contact **316** are used as an electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212**. In other words, a conductor forming the contact **268** is bonded to a conductor forming the contact **316** at the bonding surface between the first semiconductor substrate **211** and the second semiconductor substrate **212**. As above, in a case of the configuration shown in FIG. **35**, a part of the twin contact for an electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212** is formed in two divided steps.

(250) In this way, it is unnecessary to provide a deep hole which reaches the multilayer wire layer **255** from the light receiving surface, for example, unlike in forming the contact **267** of FIG. **29**. For this reason, it is possible to more simply form a contact.

(251) Although the description has been provided here of a case where a part of the twin contact used for an electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212** is formed in two divided steps, a part of a twin contact used for an electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213** may be formed in two divided steps.

(252) In addition, similarly, in the solid-state imaging device with the configuration described with reference to FIG. **11**, **12** or **20**, a part of a twin contact, used for an electrical connection between the first semiconductor substrate **211** and the second semiconductor substrate **212**, or electrical connection between the second semiconductor substrate **212** and the third semiconductor substrate **213**, may be formed in two divided steps.

(253) In other words, in the configuration (FIG. **11**) in which the aluminum pad **280** is provided in the multilayer wire layer **245** of the first semiconductor substrate **211**, a part of a twin contact used for an electrical connected between the respective semiconductor substrates may be formed in two

divided steps. In addition, in the configuration (FIG. 12) in which the aluminum pad 280 is provided in the multilayer wire layer 255 of the second semiconductor substrate 212, a part of a twin contact used for an electrical connected between the respective semiconductor substrates may be formed in two divided steps. Further, in the configuration (FIG. 20) in which the aluminum pad 280 is provided in the insulating film layer 230, a part of a twin contact used for an electrical connected between the respective semiconductor substrates may be formed in two divided steps. (254) As described with reference to FIGS. 11 to 40, in the solid-state imaging device to which the present technology is applied, the aluminum pad 280 may be provided in the multilayer wire layer 245 of the first semiconductor substrate 211, the aluminum pad 280 may be provided in the multilayer wire layer 255 of the second semiconductor substrate 212, and the aluminum pad 280 may be provided in the insulating film layer 230. In addition, as a form of electrical connection between the respective semiconductor substrates, a twin contact, a shared contact, direct bonding, and a configuration in which a part of a twin contact is formed in two divided steps may be employed.

(255) In other words, combinations as shown in FIG. 41 may be employed as embodiments of the solid-state imaging device to which the present technology is applied.

(256) In addition, in the above-described embodiments, the embodiments of the solid-state imaging device to which the present technology is applied have been described based on a three-layer stacked structure. However, the solid-state imaging device to which the present technology is applied may employ, for example, a four-layer structure in which a first semiconductor substrate, a second semiconductor substrate, a third semiconductor substrate, and a fourth semiconductor substrate are stacked.

(257) FIG. 42 shows an example of a case where the solid-state imaging device to which the present technology is applied employs the four-layer structure. FIG. 42 is a schematic diagram of a cross-sectional view illustrating a configuration according to still another embodiment of the pixel portion of the solid-state imaging device to which the present technology is applied.

(258) In the example shown in FIG. 42, a four-layer structure is employed in which a first semiconductor substrate 211, a second semiconductor substrate 212, a third semiconductor substrate 213, and a fourth semiconductor substrate 214 are stacked.

(259) In addition, similarly, the solid-state imaging device to which the present technology is applied may employ a structure of five or more layers.

(260) FIG. 43 is a block diagram illustrating a configuration example of a camera apparatus which is an electronic apparatus to which the present technology is applied.

(261) A camera apparatus 600 in FIG. 43 includes an optical unit 601 including a lens group and the like, a solid-state imaging device (imaging device) 602 which employs the above-described respective configurations of the pixels 402, and a DSP circuit 603 which is a camera signal processing circuit. In addition, the camera apparatus 600 includes a frame memory 604, a display unit 605, a recording unit 606, an operation unit 607, and a power supply unit 608. The DSP circuit 603, the frame memory 604, the display unit 605, the recording unit 606, the operation unit 607, and the power supply unit 608 are connected to each other via a bus line 609.

(262) The optical unit 601 receives incident light (image light) from a subject so as to be imaged on an imaging surface of the solid-state imaging device 602. The solid-state imaging device 602 converts a light amount of the incident light which is imaged on the imaging surface by the optical unit 601 into an electric signal in the unit of a pixel and outputs the electric signal as a pixel signal. The solid-state imaging device related to the above-described embodiments may be used as the solid-state imaging device 602.

(263) The display unit 605 includes, for example, a panel type display device such as a liquid crystal panel or an organic electroluminescence (EL) panel, and displays moving images or still images captured by the solid-state imaging device 602. The recording unit 606 records moving images or still images captured by the solid-state imaging device 602 on a recording medium such

as a video tape or a digital versatile disk (DVD).

(264) The operation unit **607** issues operation commands for various functions of the camera apparatus **600** in response to an operation by a user. The power supply unit **608** appropriately supplies a variety of power which is operation power of the DSP circuit **603**, the frame memory **604**, the display unit **605**, the recording unit **606**, and the operation unit **607**, to the supply targets.

(265) In addition, the present technology is not limited to being applied to a solid-state imaging device which detects a distribution of an incident light amount of visible light so as to capture an image, and is generally applicable to a solid-state imaging device which detects a distribution of an incidence amount of infrared rays, X rays, particles, or the like so as to capture an image, or a solid-state imaging device (physical quantity distribution detection device) such as a fingerprint detection sensor which detects distributions of the other physical quantities such as a pressure or a capacitance so as to capture an image in a broad sense.

(266) In addition, embodiments of the present technology are not limited to the above-described embodiments and may have various modifications within the scope without departing from the spirit of the present technology.

(267) Further, the present technology may have the following configurations. (1) A solid-state imaging device including a first semiconductor substrate that includes a sensor circuit provided with a photoelectric conversion portion; and a second semiconductor substrate and a third semiconductor substrate that respectively include circuits different from the sensor circuit, wherein the first semiconductor substrate is located in the uppermost layer, and the first semiconductor substrate, the second semiconductor substrate, and the third semiconductor substrate are stacked in three layers, and wherein an electrode metal element forming an electrode for external connection is disposed in the first semiconductor substrate. (2) The solid-state imaging device according to (1), wherein the sensor circuit of the first semiconductor substrate is of a rear surface irradiation type, and wherein a hole exposing the electrode metal element is opened from a light receiving surface side of the first semiconductor substrate. (3) The solid-state imaging device according to (1) or (2), wherein the second semiconductor substrate or the third semiconductor substrate includes a logical circuit or a memory circuit, and wherein the logical circuit or the memory circuit is operated based on input and output of signals to and from an external device. (4) The solid-state imaging device according to any one of (1) to (3), wherein a light blocking mechanism which blocks light incident to the photoelectric conversion portion from an opposite side to a light receiving surface of the first semiconductor substrate is provided in at least one of the first semiconductor substrate and the second semiconductor substrate. (5) The solid-state imaging device according to (4), wherein the light blocking mechanism is formed by the electrode metal element. (6) The solid-state imaging device according to (4), wherein a wire metal element used for a wire of the second semiconductor substrate is disposed in the second semiconductor substrate, and wherein the light blocking mechanism is formed by the electrode metal element and the wire metal element. (7) The solid-state imaging device according to (4), wherein the light blocking mechanism is formed by a light blocking body disposed in the second semiconductor substrate. (8) The solid-state imaging device according to (1), wherein a wire metal element used for a wire of the first semiconductor substrate is further disposed in the first semiconductor substrate, and wherein the electrode metal element is disposed at a position closer to an adhesive surface with the second semiconductor substrate than the wire metal element. (9) The solid-state imaging device according to any one of (1) to (8), wherein a contact, which penetrates through the first semiconductor substrate or the second semiconductor substrate and reaches a metal wire layer of the second semiconductor substrate or the third semiconductor substrate, a part of which reaches a wire of a wire metal layer of the first semiconductor substrate or the second semiconductor substrate, is used for electrical connection between the first semiconductor substrate and the second semiconductor substrate or electrical connection between the second semiconductor substrate and the third semiconductor substrate. (10) The solid-state imaging device according to any one of (1) to (8), wherein a part of a contact used

for electrical connection between the first semiconductor substrate and the second semiconductor substrate or electrical connection between the second semiconductor substrate and the third semiconductor substrate is formed by connecting conductors to each other at a bonding surface between the first semiconductor substrate and the second semiconductor substrate or a bonding surface between the second semiconductor substrate and the third semiconductor substrate. (11) The solid-state imaging device according to any one of (1) to (8), wherein wires exposed to a bonding surface between the first semiconductor substrate or the second semiconductor substrate and the second semiconductor substrate or the third semiconductor substrate are bonded to each other such that the first semiconductor substrate is electrically connected to the second semiconductor substrate. (12) The solid-state imaging device according to (1), wherein the first semiconductor substrate and the second semiconductor substrate are stacked such that a metal wire layer of the second semiconductor substrate comes into contact with the first semiconductor substrate, and wherein an electrode metal element forming an electrode for external connection is disposed inside a metal wire layer of the second semiconductor substrate. (13) The solid-state imaging device according to (1), wherein an insulating film layer is formed between the first semiconductor substrate and the second semiconductor substrate, wherein the first semiconductor substrate and the second semiconductor substrate are stacked such that a metal wire layer of the second semiconductor substrate comes into contact with the insulating film layer, and wherein an electrode metal element forming an electrode for external connection is disposed inside the insulating film layer. (14) An electronic apparatus including a solid-state imaging device having a first semiconductor substrate that includes a sensor circuit provided with a photoelectric conversion portion; and a second semiconductor substrate and a third semiconductor substrate that respectively include circuits different from the sensor circuit, wherein the first semiconductor substrate is located in the uppermost layer, and the first semiconductor substrate, the second semiconductor substrate, and the third semiconductor substrate are stacked in three layers, and wherein an electrode metal element forming an electrode for external connection is disposed in the first semiconductor substrate. <1> A semiconductor device comprising: a first semiconductor section including a first wiring layer at one side thereof, the first semiconductor section further including a photodiode; a second semiconductor section including a second wiring layer at one side thereof, the first and second semiconductor sections being secured together; a third semiconductor section including a third wiring layer at one side thereof, the second and the third semiconductor sections being secured together such that the first semiconductor section, second semiconductor section, and the third semiconductor section are stacked together; and a first conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication. <2> The semiconductor device of <1>, wherein the first semiconductor section, the second semiconductor section, and the third semiconductor section are stacked together in a manner such that the first wiring layer faces the second wiring layer or the second wiring layer faces the third wiring layer. <3> The semiconductor device of <2>, further comprising: a second conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication. <4> The semiconductor device of <3>, wherein at least one wiring layer electrically connected by the second conductive material is different than the wiring layers electrically connected by the first conductive material. <5> The semiconductor device of <3> or <4>, wherein at least one of the first conductive material and the second conductive material comprises two through holes which penetrate through at least one of the first semiconductor section and the second semiconductor section in a vertical direction; and wherein a first through hole of the first conductive material electrically connects to a wiring layer that is different than a wiring layer electrically connected by a second of the two through holes. <6> The semiconductor device of <3> or <4> wherein at least one of the first conductive material and the second conductive material

comprises a single through hole which penetrates through at least one of the first semiconductor section and the second semiconductor section in a vertical direction such that the at least one of the first conductive material and the second conductive material electrically contact at least two wiring layers. <7> The semiconductor device of any one of <1> to <6>, wherein a metal wire of at least one of (i) the first wiring layer, (ii) the second wiring layer, and (ii) the third wiring layer is directly bonded to a metal wire in another wiring layer. <8> The semiconductor device of <7>, wherein at least one of the wiring layers having a metal wire directly bonded is different than the wiring layers electrically connected by the first conductive material. <9> The semiconductor device of any one of <1> to <8>, further comprising a pad electrode for external connection. <10> The semiconductor device of <9>, wherein the pad is disposed such that light is blocked from one or more transistors residing in the second semiconductor section. <11> The semiconductor device of any one of <1> to <10>, wherein the first semiconductor section comprises a sensor circuit, at least one of the second semiconductor section and the third semiconductor section comprises a logical circuit, and at least one of the second semiconductor section and the third semiconductor section comprises a memory circuit. <12> A backside illumination type solid-state imaging device comprising: a first semiconductor section including a first wiring layer at one side thereof, the first semiconductor section further including a circuit region and a pixel region; a second semiconductor section including a second wiring layer at one side thereof, the first and second semiconductor sections being secured together; a third semiconductor section including a third wiring layer at one side thereof, the second and the third semiconductor sections being secured together such the first semiconductor section, second semiconductor section, and the third semiconductor section are stacked together; and a first conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication. <13> The solid-state imaging device of <12>, wherein the first semiconductor section, the second semiconductor section, and the third semiconductor section are stacked together in a manner such that the first wiring layer faces the second wiring layer or the second wiring layer faces the third wiring layer. <14> The solid-state imaging device of <13>, further comprising: a second conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication. <15> The solid-state imaging device of <14>, wherein at least one of the first conductive material and the second conductive material comprises a single through hole which penetrates through at least one of the first semiconductor section and the second semiconductor section in a vertical direction such that the at least one of the first conductive material and the second conductive material electrically contact at least two wiring layers. <16> The solid-state imaging device of any one of <12> to <15>, wherein a metal wire of at least one of (i) the first wiring layer, (ii) the second wiring layer, and (ii) the third wiring layer is directly bonded to a metal wire in another wiring layer. <17> The solid-state imaging device of any one of <12> to <16>, wherein at least one of the wiring layers having a metal wire directly bonded is different than the wiring layers electrically connected by the first conductive material. <18> The solid-state imaging device of any one of <12> to <17>, further comprising a pad electrode for external connection, wherein the pad is disposed below the pixel region such that light is blocked from one or more transistors residing in the second semiconductor section. <19> The solid-state imaging device of any one of <12> to <18>, further comprising an interlayer insulating film disposed between at least two of the semiconductor sections. <20> The solid-state imaging device of any one of <12> to <19>, wherein the first semiconductor section comprises a sensor circuit, at least one of the second semiconductor section and the third semiconductor section comprises a logical circuit, and at least one of the second semiconductor section and the third semiconductor section comprises a memory circuit. <21> An electronic apparatus including: an optical unit; and (a) a solid-state imaging device including: a first semiconductor section including a first wiring layer at one side thereof, the first semiconductor

section further including a circuit region and a pixel region; a second semiconductor section including a second wiring layer at one side thereof, the first and second semiconductor sections being secured together; (b) a third semiconductor section including a third wiring layer at one side thereof, the second and the third semiconductor sections being secured together such the first semiconductor section, second semiconductor section, and the third semiconductor section are stacked together; and (c) a first conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication. <22> The electronic apparatus of <21>, wherein the first semiconductor section, the second semiconductor section, and the third semiconductor section are stacked together in a manner such that the first wiring layer faces the second wiring layer or the second wiring layer faces the third wiring layer. <23> The electronic apparatus of <22>, further comprising: a second conductive material electrically connecting at least two of (i) the first wiring layer, (ii) the second wiring layer, and (iii) the third wiring layer such that the electrically connected wiring layers are in electrical communication, wherein at least one wiring layer electrically connected by the second conductive material is different than the wiring layers electrically connected by the first conductive material. <24> The electronic apparatus of <23>, wherein at least one of the first conductive material and the second conductive material comprises two through holes which penetrate through at least one of the first semiconductor section and the second semiconductor section in a vertical direction; and wherein a first through hole of the first conductive material electrically connects to a wiring layer that is different than a wiring layer electrically connected by a second of the two through holes. <25> The electronic apparatus of <23>, wherein at least one of the first conductive material and the second conductive material comprises a single through hole which penetrates through at least one of the first semiconductor section and the second semiconductor section in a vertical direction such that the at least one of the first conductive material and the second conductive material electrically contact at least two wiring layers. <26> The electronic apparatus of <23>, wherein a metal wire of at least one of (i) the first wiring layer, (ii) the second wiring layer, and (ii) the third wiring layer is directly bonded to a metal wire in another wiring layer, and wherein at least one of the wiring layers having a metal wire directly bonded is different than the wiring layers electrically connected by the first conductive material.

(268) It should be understood by those skilled in the art that various modifications, combinations, sub-combinations and alterations may occur depending on design requirements and other factors insofar as they are within the scope of the appended claims or the equivalents thereof.

REFERENCE SIGNS LIST

(269) **211** First semiconductor substrate **212** Second semiconductor substrate **213** Third semiconductor substrate **230** Insulating film layer **234** Photodiode **240** Copper wire **245** Multilayer wire layer **250** Copper wire **255** Multilayer wire layer **265** Contact **266** Contact **267** Contact **280** Aluminum pad **311** Contact **312** Contact **313** Contact **320** Aluminum pad **330** Aluminum pad **340** Copper wire **345** Multilayer wire layer **351** Pad hole **360** Light blocking body **370** Copper wire **401** Solid-state imaging device **402** Pixel **600** Camera apparatus **602** Solid-state imaging device

Claims

1. A light detecting device, comprising: a first section including a first semiconductor layer and a first layer including a first electrode; a second section including a second semiconductor layer, a second layer including a second electrode, and a third layer including a third electrode, wherein the second layer and the third layer are separated from another by the second semiconductor layer; a third section including a third semiconductor layer and a fourth layer including a fourth electrode; and a through electrode, wherein the through electrode is a unitary structure, wherein a first portion of the unitary structure of the through electrode extends into the second layer, wherein a second

portion of the unitary structure of the through electrode extends through the second semiconductor layer, and wherein a third portion of the unitary structure of the through electrode extends into the third layer and terminates at an electrode disposed in the third layer, wherein the first section, the second section, and the third section are stacked such that the first layer and the second layer face each other, and the third layer and the fourth layer face each other, wherein the first electrode is directly bonded to the second electrode, and wherein the third electrode is directly bonded to the fourth electrode.

2. The light detecting device according to claim 1, wherein the first layer, the second layer, the third layer, and the fourth layer are multilayer wire layers.

3. The light detecting device according to claim 1, wherein the first layer is joined to the second layer.

4. The light detecting device according to claim 3, wherein the third layer is joined to the fourth layer.

5. The light detecting device according to claim 1, wherein the through electrode is in contact with a wiring of the third layer.

6. The light detecting device according to claim 1, further comprising an electrode pad.

7. The light detecting device according to claim 6, wherein the electrode pad is disposed in the first section.

8. The light detecting device according to claim 7, wherein the electrode pad is disposed in the first section and is exposed by a pad hole.

9. The light detecting device according to claim 6, wherein the electrode pad is for connecting the light detecting device to an external device.

10. The light detecting device according to claim 1, wherein the first section includes a plurality of photoelectric conversion portions.

11. The light detecting device according to claim 10, wherein the second section includes a logic circuit.

12. The light detecting device according to claim 11, wherein the third section includes a memory circuit.

13. The light detecting device according to claim 1, wherein the first section is on a light incident surface side of the light detecting device.

14. An electronic apparatus, comprising: an optical unit including a lens group; and a light detecting device receiving incident light from the optical unit, the light detecting device including: a first section including a first semiconductor layer and a first layer including a first electrode; a second section including a second semiconductor layer, a second layer including a second electrode, and a third layer including a third electrode, wherein the second layer and the third layer are separated from another by the second semiconductor layer; a third section including a third semiconductor layer and a fourth layer including a fourth electrode; and a through electrode, wherein the through electrode is a unitary structure, wherein a first portion of the unitary structure of the through electrode extends into the second layer, wherein a second portion of the unitary structure of the through electrode extends through the second semiconductor layer, and wherein a third portion of the unitary structure of the through electrode extends into the third layer and terminates at an electrode disposed in the third layer, wherein the first section, the second section, and the third section are stacked such that the first layer and the second layer face each other, and the third layer and the fourth layer face each other, wherein the first electrode is directly bonded to the second electrode, and wherein the third electrode is directly bonded to the fourth electrode.

15. The electronic apparatus according to claim 14, wherein the first section is on a light incident surface side of the light detecting device.
