

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12418908
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Wang; Jibing et al.

User equipment-coordination set full-duplex communication

Abstract

Methods, devices, systems, and means for coordinating full-duplex communication are described in which a user equipment, UE, configured as a coordinating user equipment for a user equipment-coordination set, UECS, selects a first subset of UEs in the UECS to jointly receive downlink signals and selects a second subset of UEs in the UECS to jointly transmit uplink signals. The coordinating UE receives uplink data to transmit to the network entity and receives, from the first subset of UEs, demodulated and sampled downlink data that is received concurrently with joint-transmission of the uplink data. The coordinating UE combines the samples received from each UE in the first subset of UEs and jointly processes the combined samples to provide decoded data using the received uplink data to cancel crosstalk of uplink signals for the transmitted uplink data to downlink signals to the received downlink data.

Inventors:	Wang; Jibing (San Jose, CA), Stauffer; Erik Richard (Sunnyvale, CA)
Applicant:	Google LLC (Mountain View, CA)
Family ID:	1000008819235
Assignee:	Google LLC (Mountain View, CA)
Appl. No.:	18/006341
Filed (or PCT Filed):	July 01, 2021
PCT No.:	PCT/US2021/040093
PCT Pub. No.:	WO2022/026118
PCT Pub. Date:	February 03, 2022

Prior Publication Data

Document Identifier	Publication Date
US 20230276424 A1	Aug. 31, 2023

Related U.S. Application Data

us-provisional-application US 63058162 20200729

Publication Classification

Int. Cl.: **H04L5/14** (20060101); **H04W72/121** (20230101); **H04W72/541** (20230101)

U.S. Cl.:

CPC **H04W72/121** (20130101); **H04L5/14** (20130101); **H04W72/541** (20230101);

Field of Classification Search

CPC: H04L (5/14); H04W (72/121); H04W (72/541)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
2017/0170946	12/2016	Min et al.	N/A	N/A
2017/0237535	12/2016	Park et al.	N/A	N/A
2018/0227882	12/2017	Freda et al.	N/A	N/A
2020/0092685	12/2019	Fehrenbach et al.	N/A	N/A
2020/0127803	12/2019	Luo et al.	N/A	N/A
2020/0145175	12/2019	Hassan Hussein et al.	N/A	N/A
2020/0322962	12/2019	Wang et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
101026784	12/2006	CN	N/A
2020139811	12/2019	WO	N/A
2020142532	12/2019	WO	N/A
2020186097	12/2019	WO	N/A
2022026118	12/2021	WO	N/A

OTHER PUBLICATIONS

“Foreign Office Action”, IN Application No. 202347006147, Mar. 18, 2024, 6 pages. cited by applicant

“International Preliminary Report on Patentability”, Application No. PCT/US2021/040093, Nov. 4, 2022, 8 pages. cited by applicant

“International Search Report and Written Opinion”, Application No. PCT/US2021/040093, Oct. 22, 2021, 12 pages. cited by applicant

“Written Opinion”, Application No. PCT/US2021/040093, Jul. 11, 2022, 8 pages. cited by applicant

“Coordinated multi-cell transmission for LTE-Advanced downlink”, R1-082896, Aug. 2008, 4 pages. cited by applicant

“Foreign Office Action”, CN Application No. 202180059460.X, Mar. 25, 2025, 18 pages. cited by applicant

Primary Examiner: Onamuti; Gbemileke J

Attorney, Agent or Firm: Colby Nipper PLLC

Background/Summary

RELATED APPLICATION(S) (1) This application is a national stage entry of International Application No. PCT/US2021/040093, filed Jul. 1, 2021, which claims the benefit of U.S. Provisional Application No. 63/058,162, filed Jul. 29, 2020, the disclosures of which are incorporated herein by reference in their entirety.

BACKGROUND

(1) The evolution of wireless communication to fifth generation (5G) and sixth generation (6G) standards and technologies provides higher data rates and greater capacity with improved reliability

and lower latency which enhances mobile broadband services. 5G and 6G technologies also provide new classes of services for vehicular networking, fixed wireless broadband, and the Internet of Things (IoT).

(2) A unified air interface, which utilizes licensed, unlicensed, and shared license radio spectrum in multiple frequency bands is one aspect of enabling the capabilities of 5G and 6G systems. The unified air interface utilizes radio spectrum in bands below 1 GHz (sub-gigahertz), below 6 GHz (sub-6 GHz), and above 6 GHz. Radio spectrum above 6 GHz includes millimeter wave (mmWave) and terahertz (THz) frequency bands that provide wide channel bandwidths to support higher data rates for wireless broadband. Radio channels in these frequency bands are allocated for communication using time division duplexing or frequency division duplexing. However, there is an opportunity to improve spectrum utilization with full-duplex communication.

SUMMARY

(3) This summary is provided to introduce simplified concepts of user equipment-coordination set full-duplex communication. The simplified concepts are further described below in the Detailed Description. This summary is not intended to identify essential features of the claimed subject matter nor is it intended for use in determining the scope of the claimed subject matter.

(4) In aspects, methods, devices, systems, and means for coordinating full-duplex communication are described in which a user equipment (UE) configured as a coordinating user equipment for a user equipment-coordination set (UECS) in a wireless communications network selects a first subset of UEs in the UECS to jointly receive downlink signals and selects a second subset of UEs in the UECS to jointly transmit uplink signals. The coordinating UE transmits an indication that the UECS is capable of full-duplex communication to a network entity and receives, from the network entity, a resource grant for a target UE in the UECS. The coordinating UE receives uplink data to transmit to the network entity and receives, from the first subset of UEs, demodulated and sampled downlink data that is received concurrently with joint-transmission of the uplink data by the second subset of UEs. The coordinating UE combines the samples received from each UE in the first subset of UEs and jointly processes the combined samples to provide decoded data using the received uplink data to cancel crosstalk of uplink signals for the transmitted uplink data from downlink signals for the received downlink data.

(5) In aspects, methods, devices, systems, and means for coordinating full-duplex communication are described in which a base station receives an indication from a user equipment-coordination set (UECS) that the UECS is capable of full-duplex communication, the indication including an indication of a full-duplex bandwidth for the full-duplex communication. Based on the indication that the UECS is capable of full-duplex bandwidth, the base station allocates downlink resources and uplink resources for full-duplex communication with a target user equipment, UE, in the UECS and transmits a first resource grant to the UECS, the first resource grant including an indication of the downlink resources and the uplink resources. The base station receives uplink signals for uplink data from the UECS using the uplink resources and, using downlink data that is concurrently transmitted to the UECS with the received uplink signals, processes the received uplink signals to provide decoded data using the downlink data to cancel interference from downlink signals for the transmitted downlink data to received uplink signals.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

(1) The details of one or more aspects of user equipment-coordination set full-duplex communication are described below. The use of the same reference numbers in different instances in the description and the figures indicate similar elements:

(2) FIG. 1 illustrates an example operating environment in which aspects of user equipment-

coordination set full-duplex communication can be implemented.

(3) FIG. 2 illustrates an example device diagram of a user equipment and a serving cell base station.

(4) FIG. 3 illustrates an air interface resource that extends between a user equipment and a base station and with which various aspects of user equipment-coordination set full-duplex communication can be implemented.

(5) FIG. 4 illustrates an example environment in which various aspects of user equipment-coordination set full-duplex communication can be implemented.

(6) FIG. 5 illustrates various allocations of an air interface resource that extends between a UECS and a base station and with which various aspects of user equipment-coordination set full-duplex communication can be implemented.

(7) FIG. 6 illustrates an example environment in which various aspects of user equipment-coordination set full-duplex communication can be implemented.

(8) FIG. 7 illustrates data and control transactions between devices of a user-equipment-coordination set and a base station in accordance with aspects of user equipment-coordination set full-duplex communication.

(9) FIG. 8 illustrates an example method of user equipment-coordination set full-duplex communication as generally related to the coordinating user equipment of the user equipment-coordination set in accordance with aspects of the techniques described herein.

(10) FIG. 9 illustrates an example method of user equipment-coordination set full-duplex communication as generally related to a base station communicating with a user equipment-coordination set in accordance with aspects of the techniques described herein.

DETAILED DESCRIPTION

(11) This document describes methods, devices, systems, and means for coordinating full-duplex communication in which a user equipment (UE) configured as a coordinating user equipment for a user equipment-coordination set (UECS) in a wireless communications network selects a first subset of UEs in the UECS to jointly receive downlink signals and selects a second subset of UEs in the UECS to jointly transmit uplink signals. The coordinating UE transmits an indication that the UECS is capable of full-duplex communication to a network entity and receives, from the network entity, a resource grant for a target UE in the UECS. The coordinating UE receives, from the first subset of UEs, demodulated and sampled downlink data that is jointly-received by the first subset of UEs concurrently with modulated and coded uplink data that is joint-transmitted by the second subset of UEs. The coordinating UE combines the samples received from each UE in the first subset of UEs and jointly processes the combined samples to provide decoded data using the received uplink data to cancel crosstalk of uplink signals for the transmitted uplink data from downlink signals for the received downlink data.

(12) A UECS is formed by multiple UEs assigned as a group to function together, similarly to a distributed antenna, for the benefit of a particular UE (e.g., target UE). The UECS includes a coordinating UE that coordinates joint transmission of uplink signals and/or joint reception of downlink signals for the target UE or multiple target UEs in the UECS. By combining antennas and transmitters of multiple UEs in the UECS, the effective transmit power of the target UE is significantly increased, and the effective signal quality is greatly improved. Similarly, by combining antennas and receivers of multiple UEs in the UECS, the effective receive power of the target UE is significantly increased, and the effective signal quality is greatly improved.

(13) Multiple UEs can each receive downlink data transmissions from the base station. Unlike conventional relay techniques, these UEs do not decode the downlink transmissions into data packets and then forward the data packets to a destination. Rather, the UEs demodulate and sample the downlink transmissions to produce I/Q samples. The UEs determine where to forward the I/Q samples of the downlink transmissions, such as to a coordinating UE for decoding. Note that a single UE may simultaneously have the roles of a coordinating UE and a target UE. In aspects, the

target UE may be included in a subset of target UEs within the UECS. The coordinating UE receives the I/Q samples from the other UEs in the UECS and stores the I/Q samples in a buffer memory for decoding. Then, the coordinating UE synchronizes and decodes the stored I/Q samples into data packets for transmission to the target UE(s). Accordingly, the processing of the I/Q samples occurs at the coordinating UE. In this way, the UECS acts as a distributed antenna for the target UE.

(14) When a target UE has uplink data to send to a base station, the target UE transmits the uplink data to the coordinating UE, which uses a local wireless network to distribute the uplink data to each UE in the UE-coordination set. Each UE in the UE-coordination set synchronizes with the base station for timing information and its data transmission resource assignment. Then, all the UEs in the UE-coordination set jointly transmit the uplink data to the base station. The base station receives the jointly-transmitted uplink data from the UEs and processes the combined signal to decode the uplink data from the target UE.

(15) Full-duplex communication can improve spectral efficiency (utilization) for wireless communication. When uplink and downlink communications concurrently utilize the same frequency for full-duplex communication, the output power of a transmitter at a device (e.g., a UE or a base station) can make reception challenging for the device's receiver. For example, the transmitter output power of the device may be 100 dB or greater than the signal strength of the signal the device is attempting to receive. The isolation between the transmitter output and the receiver input of the device may be insufficient to handle the disparity between transmit and receive signal powers resulting in the transmitter's output interfering with the receiver's ability (e.g., saturating the input circuitry of the receiver) to receive and decode a desired receive signal.

(16) In aspects, a UECS can exploit the geographic separation between UEs in the UECS for full-duplex communication on the same frequency or channel when communicating with a base station or an Active Coordination Set (ACS) of base stations. The geographic (physical) separation between UEs in a UECS provides greater isolation between receivers of downlink signals and transmitters of uplink signals than can be provided by a co-located transmitter and receiver in a single UE.

(17) In one aspect, a coordinating UE determines a first subset of UEs in the UECS to participate in joint-reception and a second subset of UEs to participate in joint-transmission. Any UE in the UECS can be assigned to joint-reception or to joint-transmission, but no UE can be assigned to both. In a further aspect, the role of the coordinating UE can be shared by assigning a first UE the role of coordinating joint-reception (RX-coordinating UE) and assigning a second UE the role of coordinating joint-transmission (TX-coordinating UE). In this aspect, the TX-coordinating UE may share information related to the joint-transmissions with the RX-coordinating UE to assist the RX-coordinating UE in canceling crosstalk from the joint-transmission from jointly-received signals.

Example Environment

(18) FIG. 1 illustrates an example environment **100**, which includes multiple user equipment **110** (UE **110**), illustrated as UE **111**, UE **112**, UE **113**, and UE **114**. When in communication range of a base station, each UE **110** can communicate with one or more base stations **120** (illustrated as base stations **121** and **122**) through one or more wireless communication links **130** (wireless link **130**), illustrated as wireless links **131** and **132**. When individual UEs, such as the UE **111**, the UE **112**, the UE **113**, and the UE **114** are individually out of communication range of a base station, those UEs can form a UECS and use joint-transmission and joint-reception to communicate with a base station. Each UE **110** in a UECS (illustrated as UE **111**, UE **112**, UE **113**, and the UE **114**) can communicate with a coordinating UE of the UECS and/or a target UE in the UECS through one or more local wireless network connections (e.g., WLAN, Bluetooth, NFC, a personal area network (PAN), WiFi-Direct, IEEE 802.15.4, ZigBee, Thread, millimeter wavelength communication (mmWave), or the like) such as local wireless network connections **133**, **134**, **135**, and **136**.

Although illustrated as a smartphone, the UE **110** may be implemented as any suitable computing

or electronic device, such as a mobile communication device, a modem, cellular phone, gaming device, navigation device, media device, laptop computer, desktop computer, tablet computer, smart appliance, vehicle-based communication system, an Internet-of-things (IoT) device (e.g., sensor node, controller/actuator node, combination thereof), and the like. The base stations **120** (e.g., an Evolved Universal Terrestrial Radio Access Network Node B, E-UTRAN Node B, evolved Node B, eNodeB, eNB, Next Generation Node B, gNode B, gNB, ng-eNB, or the like) may be implemented in a macrocell, microcell, small cell, picocell, distributed base station or the like, or any combination or future evolution thereof.

(19) The base stations **120** communicate with a UECS or a user equipment **110** using the wireless links **131** and **132**, respectively, which may be implemented as any suitable type of wireless link. The wireless links **131** and **132** include control and data communication, such as downlink of data and control information communicated from the base stations **120** to the user equipment **110**, uplink of other data and control information communicated from the user equipment **110** to the base stations **120**, or both. The wireless links **130** may include one or more wireless links (e.g., radio links) or bearers implemented using any suitable communication protocol or standard, or combination of communication protocols or standards, such as 3rd Generation Partnership Project Long-Term Evolution (3GPP LTE), Fifth Generation New Radio (5G NR), and future evolutions. Multiple wireless links **130** may be aggregated in a carrier aggregation to provide a higher data rate for the UE **110**. Multiple wireless links **130** from multiple base stations **120** may be configured for Coordinated Multipoint (CoMP) communication with the UE **110**. For example, an Active Coordination Set (ACS) of base stations can communicate with the UE **111** using CoMP communication. The ACS may be a component of, or used to implement, a user-centric no-cell (UCNC) network architecture.

(20) The base stations **120** are collectively a Radio Access Network **140** (e.g., RAN, Evolved Universal Terrestrial Radio Access Network, E-UTRAN, 5G NR RAN, or NR RAN). The base stations **121** and **122** in the RAN **140** are connected to a core network **150**. The base stations **121** and **122** connect, at **102** and **104** respectively, to the core network **150** through an NG2 interface for control-plane signaling and using an NG3 interface for user-plane data communications when connecting to a 5G core network, or using an S1 interface for control-plane signaling and user-plane data communications when connecting to an Evolved Packet Core (EPC) network. The base stations **121** and **122** can communicate using an Xn Application Protocol (XnAP) through an Xn interface or using an X2 Application Protocol (X2AP) through an X2 interface, at **106**, to exchange user-plane and control-plane data. The user equipment **110** may connect, via the core network **150**, to public networks, such as the Internet **160** to interact with a remote service **170**.

Example Devices

(21) FIG. 2 illustrates an example device diagram **200** of a user equipment and a base station. In aspects, the device diagram **200** describes devices that can implement various aspects of user equipment-coordination set full-duplex communication. Included in FIG. 2 are the multiple UE **110** and the base stations **120**. The multiple UE **110** and the base stations **120** may include additional functions and interfaces that are omitted from FIG. 2 for the sake of illustration clarity. The UE **110** includes antennas **202**, a radio frequency front end **204** (RF front end **204**), and radio-frequency transceivers (e.g., an LTE transceiver **206** and a 5G NR transceiver **208**) for communicating with base stations **120** in a 5G RAN and/or an E-UTRAN. The UE **110** includes one or more additional transceivers (e.g., local wireless network transceiver **210**) for communicating over one or more wireless local wireless networks (e.g., WLAN, Bluetooth, NFC, a personal area network (PAN), WiFi-Direct, IEEE 802.15.4, ZigBee, Thread, mmWave, or the like) with at least the coordinating UE of the UECS. The RF front end **204** of the UE **110** can couple or connect the LTE transceiver **206**, the 5G NR transceiver **208**, and the local wireless network transceiver **210** to the antennas **202** to facilitate various types of wireless communication.

(22) The antennas **202** of the UE **110** may include an array of multiple antennas that are configured

similar to or differently from each other. The antennas **202** and the RF front end **204** can be tuned to, and/or be tunable to, one or more frequency bands defined by the 3GPP LTE and 5G NR communication standards and implemented by the LTE transceiver **206**, and/or the 5G NR transceiver **208**. Additionally, the antennas **202**, the RF front end **204**, the LTE transceiver **206**, and/or the 5G NR transceiver **208** may be configured to support beamforming for the transmission and reception of communications with the base stations **120**. By way of example and not limitation, the antennas **202** and the RF front end **204** can be implemented for operation in sub-gigahertz bands, sub-6 GHz bands, and/or above 6 GHz bands that are defined by the 3GPP LTE and 5G NR communication standards. In addition, the RF front end **204** can be tuned to, and/or be tunable to, one or more frequency bands defined and implemented by the local wireless network transceiver **210** to support transmission and reception of communications with other UEs in the UECS over a local wireless network.

(23) The UE **110** includes sensor(s) **212** can be implemented to detect various properties such as temperature, supplied power, power usage, battery state, or the like. As such, the sensors **212** may include any one or a combination of temperature sensors, thermistors, battery sensors, and power usage sensors.

(24) The UE **110** also includes processor(s) **214** and computer-readable storage media **216** (CRM **216**). The processor **214** may be a single core processor or a multiple core processor composed of a variety of materials, such as silicon, polysilicon, high-K dielectric, copper, and so on. The computer-readable storage media described herein excludes propagating signals. CRM **216** may include any suitable memory or storage device such as random-access memory (RAM), static RAM (SRAM), dynamic RAM (DRAM), non-volatile RAM (NVRAM), read-only memory (ROM), or Flash memory useable to store device data **218** of the UE **110**. The device data **218** includes user data, multimedia data, beamforming codebooks, applications, and/or an operating system of the UE **110**, which are executable by processor(s) **214** to enable user-plane communication, control-plane signaling, and user interaction with the UE **110**.

(25) CRM **216** also includes a communication manager **220** (e.g., a communication manager application **220**). Alternately or additionally, the communication manager **220** may be implemented in whole or part as hardware logic or circuitry integrated with or separate from other components of the UE **110**. In at least some aspects, the communication manager **220** configures the RF front end **204**, the LTE transceiver **206**, the 5G NR transceiver **208**, and/or the local wireless network transceiver **210** to implement the techniques described herein for user equipment-coordination set full-duplex communication.

(26) The device diagram for the base stations **120**, shown in FIG. 2, includes a single network node (e.g., a gNode B). The functionality of the base stations **120** may be distributed across multiple network nodes or devices and may be distributed in any fashion suitable to perform the functions described herein. The base stations **120** include antennas **252**, a radio frequency front end **254** (RF front end **254**), one or more LTE transceivers **256**, and/or one or more 5G NR transceivers **258** for communicating with the UE **110**. The RF front end **254** of the base stations **120** can couple or connect the LTE transceivers **256** and the 5G NR transceivers **258** to the antennas **252** to facilitate various types of wireless communication. The antennas **252** of the base stations **120** may include an array of multiple antennas that are configured similar to or differently from each other. The antennas **252** and the RF front end **254** can be tuned to, and/or be tunable to, one or more frequency band defined by the 3GPP LTE and 5G NR communication standards, and implemented by the LTE transceivers **256**, and/or the 5G NR transceivers **258**. Additionally, the antennas **252**, the RF front end **254**, the LTE transceivers **256**, and/or the 5G NR transceivers **258** may be configured to support beamforming, such as Massive-MIMO, for the transmission and reception of communications with any UE **110** in a UECS.

(27) The base stations **120** also include processor(s) **260** and computer-readable storage media **262** (CRM **262**). The processor **260** may be a single core processor or a multiple core processor

composed of a variety of materials, such as silicon, polysilicon, high-K dielectric, copper, and so on. CRM **262** may include any suitable memory or storage device such as random-access memory (RAM), static RAM (SRAM), dynamic RAM (DRAM), non-volatile RAM (NVRAM), read-only memory (ROM), or Flash memory useable to store device data **264** of the base stations **120**. The device data **264** includes network scheduling data, radio resource management data, beamforming codebooks, applications, and/or an operating system of the base stations **120**, which are executable by processor(s) **260** to enable communication with the UE **110**.

(28) CRM **262** also includes a base station manager **266** (e.g., base station manager application **266**). Alternately or additionally, the base station manager **266** may be implemented in whole or part as hardware logic or circuitry integrated with or separate from other components of the base stations **120**. In at least some aspects, the base station manager **266** configures the LTE transceivers **256** and the 5G NR transceivers **258** for communication with the UE **110**, as well as communication with a core network. The base stations **120** include an inter-base station interface **268**, such as an Xn and/or X2 interface, which the base station manager **266** configures to exchange user-plane and control-plane data between another base station **120**, to manage the communication of the base stations **120** with the UE **110**. The base stations **120** include a core network interface **270** that the base station manager **266** configures to exchange user-plane and control-plane data with core network functions and entities.

Air Interface Resources

(29) FIG. 3 illustrates an air interface resource that extends between a user equipment and a base station and with which various aspects of user equipment-coordination set full-duplex communication can be implemented. The air interface resource **302** can be divided into resource units **304**, each of which occupies some intersection of frequency spectrum and elapsed time. A portion of the air interface resource **302** is illustrated graphically in a grid or matrix having multiple resource blocks **310**, including example resource blocks **311**, **312**, **313**, **314**. An example of a resource unit **304** therefore includes at least one resource block **310**. As shown, time is depicted along the horizontal dimension as the abscissa axis, and frequency is depicted along the vertical dimension as the ordinate axis. The air interface resource **302**, as defined by a given communication protocol or standard, may span any suitable specified frequency range, and/or may be divided into intervals of any specified duration. Increments of time can correspond to, for example, milliseconds (mSec). Increments of frequency can correspond to, for example, megahertz (MHz).

(30) In example operations generally, the base stations **120** allocate portions (e.g., the resource units **304**) of the air interface resource **302** for uplink and downlink communications. Each resource block **310** of network access resources may be allocated to support respective wireless communication links **130** of multiple user equipment **110**. In the lower left corner of the grid, the resource block **311** may span, as defined by a given communication protocol, a specified frequency range **306** and comprise multiple subcarriers or frequency sub-bands. The resource block **311** may include any suitable number of subcarriers (e.g., 12) that each correspond to a respective portion (e.g., 15 kHz) of the specified frequency range **306** (e.g., 180 kHz). The resource block **311** may also span, as defined by the given communication protocol, a specified time interval **308** or time slot (e.g., lasting approximately one-half millisecond or seven orthogonal frequency-division multiplexing (OFDM) symbols). The time interval **308** includes subintervals that may each correspond to a symbol, such as an OFDM symbol. As shown in FIG. 3, each resource block **310** may include multiple resource elements **320** (REs) that correspond to, or are defined by, a subcarrier of the frequency range **306** and a subinterval (or symbol) of the time interval **308**. Alternatively, a given resource element **320** may span more than one frequency subcarrier or symbol. Thus, a resource unit **304** may include at least one resource block **310**, at least one resource element **320**, and so forth.

(31) In example implementations, multiple user equipment **110** (one of which is shown) are

communicating with the base stations **120** (one of which is shown) through access provided by portions of the air interface resource **302**. The base station manager **266** (shown in FIG. 2) may determine a respective data-rate, type of information, or amount of information (e.g., data or control information) to be communicated (e.g., transmitted) by the user equipment **110**. The base station manager **266** then allocates one or more resource blocks **310** to each user equipment **110** based on the determined data rate or amount of information.

(32) Additionally, or in the alternative to block-level resource grants, the base station manager **266** may allocate resource units at an element-level. Thus, the base station manager **266** may allocate one or more resource elements **320** or individual subcarriers to different user equipment **110**. By so doing, one resource block **310** can be allocated to facilitate network access for multiple user equipment **110**. Accordingly, the base station manager **266** may allocate, at various granularities, one or up to all subcarriers or resource elements **320** of a resource block **310** to one user equipment **110** or divided across multiple user equipment **110**, thereby enabling higher network utilization or increased spectrum efficiency.

(33) The base station manager **266** can therefore allocate air interface resource **302** by resource unit **304**, resource block **310**, frequency carrier, time interval, resource element **320**, frequency subcarrier, time subinterval, symbol, spreading code, some combination thereof, and so forth. Based on respective allocations of resource units **304**, the base station manager **266** can transmit respective messages to the multiple user equipment **110** indicating the respective allocation of resource units **304** to each user equipment **110**. Each message may enable a respective user equipment **110** to queue the information or configure the LTE transceiver **206** and/or 5G NR transceiver **208** to communicate via the allocated resource units **304** of the air interface resource **302**.

User Equipment-Coordination Set Full-Duplex Communication

(34) FIG. 4 illustrates an example implementation **400** of user equipment-coordination set full-duplex communication. The illustrated example includes a base station **121** and a UECS **402** that includes UE **111**, UE **112**, UE **113**, UE **114**, and UE **115**. Although, for the sake of illustration clarity, the UECS in FIG. 4 is illustrated as including five UEs, any number of UEs greater than one may be included in a UECS. In the UECS **402**, the UE **111** is acting as the coordinating UE for the UECS **402**. Although not illustrated for the sake of visual clarity, the UEs in the UECS communicate with each other using local wireless network connections as discussed above.

(35) In aspects, the coordinating UE **111** selects a first subset **404** of UEs in the UECS **402** to participate in joint-reception of downlink (DL) signals (a DL-coordinating subset **404**) and selects a second subset **406** of UEs to participate in joint-transmission of uplink (UL) signals (an UL-coordinating subset **406**). The coordinating UE **111** can participate in joint-reception, joint-transmission, or neither joint-reception nor joint-transmission. For example, in the UECS **402**, the coordinating UE has selected itself, the UE **112**, and the UE **113** for the DL-coordinating subset **404** for joint-reception of downlink signals **408** from the base station **121** and the coordinating UE has selected the UE **114**, and the UE **115** for UL-coordinating subset **406** for joint-transmission of uplink signals **410** to the base station **121**. The coordinating UE **111** can select the subsets of UEs in any suitable manner such as including some or all of the UEs in the two subsets or selecting UEs for the respective subsets to provide the greatest physical isolation between the transmitting UEs and the receiving UEs. For example, the coordinating UE **111** can use location information of the UEs in the UECS to select UEs for the two subsets that provide the greatest isolation or a minimum acceptable isolation between the joint-transmission UEs (the DL-coordinating subset **404**) and the joint-reception UEs (the UL-coordinating subset **406**). For example, the coordinating UE **111** selects UEs for the two subsets to provide an amount of isolation (e.g., at least 50 dB of isolation) that allows the joint-processing to cancel crosstalk from joint-transmissions to joint-receptions.

(36) The coordinating UE **111** (or another UE, for example a target UE) can cancel crosstalk from joint-transmissions to joint-receptions during joint-processing of the received downlink signals. For

example, in the UECS **402**, the joint-transmissions by the UEs **114** and **115** may cause interference to the joint-receptions by the UEs **111**, **112**, and **113**. Based on joint-processing of uplink signals for joint-transmission, the coordinating UE **111** can cancel crosstalk from joint-transmissions to joint-receptions using knowledge of the uplink signals for joint-transmission and the timing of the joint-transmission.

(37) Alternatively or additionally, the role of the coordinating UE for full-duplex communication can be shared by two UEs by assigning a first UE the role of coordinating joint-reception (RX-coordinating UE) and assigning a second UE the role of coordinating joint-transmission (TX-coordinating UE). When the role of the coordinating UE is shared, the TX-coordinating UE may share information related to the joint-transmissions with the RX-coordinating UE to assist the RX-coordinating UE in canceling crosstalk from the joint-transmission on the jointly-received signals.

(38) Any single UE in the UL-coordinating subset **406** or in the DL-coordinating subset **404** may not overlap their transmissions and receptions in a single time interval (e.g., in a single slot or symbol), but the UEs composing the UL-coordinating subset **406** and the DL-coordinating subset **404** can change dynamically. For example, a target DL UE (e.g., the UE **112**) in the DL-coordinating subset **404** switches to a TX-coordinating UE role for the UL-coordinating subset **406**. Meanwhile, the DL-coordinating subset **404** continues to perform DL reception for the target DL UE **112**.

(39) In other aspects, the base station **121** can allocate the downlink and uplink frequency resources based on the UECS **402** being capable of full-duplex communication. FIG. 5 illustrates various allocations of an air interface resource that extends between a UECS and a base station and with which various aspects of user equipment-coordination set full-duplex communication can be implemented. When the UECS **402** is not operating using full-duplex communication, the base station **121** can allocate resources for Time Division Duplex (TDD) communication as illustrated in the columns of resource elements at **502** for downlink (DL) and uplink (UL) communication or the base station **121** can allocate resources for Frequency Division Duplex (FDD) communication as illustrated in the column of resource elements at **504**. The coordinating UE **111** indicates the full-duplex capability of the UECS **402** to the base station **121**, for example, when the coordinating UE **111** can determine subsets of joint-transmission and joint-reception UEs that have sufficient isolation to support joint-processing of full-duplex communication with the base station **121**. For example, the coordinating UE **111** indicates the full-duplex capability of the UECS **402** in a capability information element that includes fields for a UECS Radio Network Temporary Identifier (UECS-RNTI) and an associated full-duplex bandwidth that the coordinating UE **111** determines that the UECS **402** can support. For example, the coordinating UE **111** estimates the isolation between the joint-transmission UEs and the joint-reception UEs (e.g., based on the locations of the UEs in the UECS) to determine a bandwidth for which the joint-processing in the UECS can cancel crosstalk. For example, if the coordinating UE **111** estimates a relatively-lower isolation, the coordinating UE **111** indicates a narrower full-duplex bandwidth (e.g., a 10 MHz bandwidth) or if the coordinating UE **111** estimates a relatively-higher isolation, the coordinating UE **111** indicates a wider full-duplex bandwidth (e.g., a 100 MHz bandwidth).

(40) Based on indicated full-duplex bandwidth, the base station **121** allocates uplink and downlink resources at the same time slot and on the same frequency to the joint-transmission UEs and the joint-reception UEs in the UECS **402** and transmits a resource grant to the coordinating UE that indicates the allocated resources. For example, the base station **121** allocates all the resource elements in column **506** for full-duplex (DL and UL) communication between the base station **121** and the UECS **402**. The resources for the uplink and the downlink can be the same or different within the same frequency range, such as shown in column **508**. If the indicated full-duplex bandwidth indicates that the UECS **402** cannot perform crosstalk cancellation and thus full-duplex communication, the base station **121** will not grant resources for concurrent uplink and downlink communication on the same time slot for the UEs in the UECS **402**.

(41) The base station **121** can schedule a DL grant and a UL grant for the same target UE in the UECS **402** or different target UEs in the UECS **402**. The resource grant, different from the resource grant(s) to the UECS for the target UE when the UEs in the UECS jointly receive or jointly transmit using non-full-duplex communication on behalf of the target UE, can be granted by base station **121** or by the coordinating UE **111** master UE using the local wireless network in the UECS **402**. For example, if the base station **121** scheduled DL and UL communications concurrently on the same time slot for the UE **112**, the coordinating UE **111** can still determine that the UEs **111**, **112**, and **113** will perform the joint-reception for the downlink data for UE **112**, while the UEs **114** and **115** perform the joint-transmission of the UL data of UE **112**, with the coordinating UE **111** coordinating crosstalk cancellation of the uplink signal to the downlink reception for the UE **112**.

(42) In a further aspect, the ability of the UECS to perform full-duplex communication can vary over time, for example, based on changes in isolation due to movement of the UEs in the UECS, departure of a UE from the UECS, or addition of a UE to the UECS. The coordinating UE **111** and/or the base station **121** can determine changes in the ability of the joint-processing to cancel crosstalk during full-duplex communication based on any suitable indication or measurement of the full-duplex communication. In a first example, the coordinating UE **111** and/or the base station **121** can monitor a ratio of negative acknowledgements (NACKs) to acknowledgments (ACKs) for downlink communications where an increasing ratio of NACKs to ACKs indicates that the crosstalk canceling by the joint-processing is decreasing in effectiveness. The coordinating UE **111** may evaluate the ratio of NACKs to ACKs against a threshold value and, based on the ratio of NACKs to ACKs exceeding the threshold value, the coordinating UE **111** determines an updated value for the full-duplex bandwidth and transmits an indication of that updated full-duplex bandwidth to the base station **121** to indicate that the UECS **402** can only support a narrower bandwidth for full-duplex communication or that the UECS **402** can no longer support full-duplex communication. Alternatively or additionally, the base station **121** may evaluate the ratio of NACKs to ACKs that it receives for downlink data against a threshold value and based on determining that the ratio of NACKs to ACKs exceeds the threshold, the base station changes the allocation of resources for full-duplex communication to reduce the channel bandwidth for full-duplex communication with the UECS **402**, reduces the overlap of DL and UL resources for full-duplex communication, or reallocates resources to terminate full-duplex communication with the UECS **402**.

(43) In a second example, the base station **121** can allocate a partial overlap of resource elements for full-duplex communication with the UECS **402** to evaluate the crosstalk-cancellation capability of the joint-processing in the UECS **402**. The base station **121** allocates a first portion of the resource elements for full-duplex communication to overlap in time and frequency and a second portion to not overlap in time and/or frequency. For example, the base station **121** allocates the resource elements in a time slot (column **508**) based on frequency such that fifty percent of the resource elements are allocated for full-duplex communication (DL/UL) and the remaining resource elements are allocated for DL or UL communication with the UECS **402**. In another example, the base station **121** allocates the resource elements based on time slots (illustrated in the columns **510**), such that one-third of the resource elements are allocated for full-duplex communication (DL/UL), another one-third of the resource elements are allocated for DL communication, and the remaining third are allocated for UL communications with the UECS **402**. The base station **121** can allocate resource elements in any suitable manner based on time and/or frequency to allocate varying proportions of resources to downlink, uplink, and/or full-duplex communication with the UECS **402**. The coordinating UE **111** determines a signal quality metric (e.g., a signal to noise ratio (SNR) or a signal to noise and interference ratio (SINR)) for the first portion of the resource blocks (the overlapped resource blocks) and the second portion of the resource blocks (the non-overlapped resource blocks) to determine the efficacy of joint-processing to cancel UL to DL crosstalk. Based on the determination, the coordinating UE **111** can determine

an updated value for the full-duplex bandwidth and transmit an indication of that updated full-duplex bandwidth to the base station **121** to indicate that the UECS **402** can only support a narrower bandwidth for full-duplex communication or that the UECS **402** can no longer support full-duplex communication.

(44) User Equipment-Coordination Set Full-Duplex Communication with an Active Coordination Set

(45) FIG. **6** illustrates an example implementation **600** of user equipment-coordination set full-duplex communication. The illustrated example includes an active coordination set (ACS) **602** that includes the base station **121** and the base station **122**, and the UECS **402** that includes the UE **111**, UE **112**, UE **113**, UE **114**, and UE **115**. Although, for the sake of illustration clarity, the UECS in FIG. **6** is illustrated as including five UEs, any number of UEs greater than one may be included in a UECS. In the UECS **402**, the UE **111** is acting as the coordinating UE for the UECS **402**.

Although not illustrated for the sake of clarity, the UEs in the UECS communicate with each other using local wireless network connections as discussed above. Although, for the sake of illustration clarity, the ACS in FIG. **6** is illustrated as including two base stations, any number of base stations greater than one may be included in an ACS.

(46) In the ACS **602**, the base station **121** is acting as a coordinating (master) base station for the joint transmission and/or joint reception between the ACS **602** and the UECS **402**. From the perspective of the UECS **402** and the UEs included in the UECS **402**, the operations of full-duplex communication are the same when communicating with the ACS **602** as those described for communicating with the base station **121** as described above with respect to FIG. **4**. Which one of the base stations in the ACS **602** is the coordinating base station is transparent to the UECS **402**, and the coordinating base station can change as base stations are added and/or removed from the ACS. The coordinating base station coordinates control-plane and user-plane communications for the joint communication with the UECS **402** via the Xn interface **106** (or a similar 4G, 5G, or 6G interface) to the base station **122** and maintains the user-plane context between the target UE in the UECS **402** and the core network **150**. The coordinating base station **121** may use proprietary or standards-based messaging, procedures, and/or protocols for coordination of operations of the ACS **602**. The coordinating base station schedules air interface resources for the joint communication for the UECS **402** and the base stations **121** and **122**, based on the ACS associated with the target UE.

(47) In aspects of full-duplex communication, as compared to full-duplex communication with a single base station, an ACS can provide higher isolation (e.g., 60 to 70 dB) between downlink transmissions and uplink receptions by using a first base station **121** in the ACS **602** for downlink transmissions to the UECS **402** and using the second base station **122** in the ACS **602**, that is physically separated from the base station **121**, for downlink transmissions. As illustrated in FIG. **6**, the base station **121** transmits downlink signals **408** to the DL-coordinating subset **404** of UEs (the UEs **111**, **112**, and **113**) in the UECS **402** and the base station **122** receives uplink signals from the UL-coordinating subset **406** of UEs (the UEs **114** and **115**). Although in FIG. **6**, the base station **121** is illustrated as transmitting downlink signals to the DL-coordinating subset **404** of UEs and the base station **122** is illustrated as receiving uplink signals from the UL-coordinating subset **406** of UEs, either base station can transmit the downlink signals with the other base station receiving the uplink signals. Although base station **121** is described as acting in the role of the coordinating base station for the ACS **602**, which base station in the ACS is the coordinating base station is independent from whether the base station is transmitting the downlink signals or receiving the uplink signals for the ACS **602**. The coordinating base station **121** can provide the downlink data and associated transmission timings and resource allocations to the base station **122** using the Xn interface **106** to enable the base station **122** to use that information to cancel crosstalk to the uplink signals from the concurrently transmitted downlink signals.

(48) In further aspects, the base station **122** receives indications of the full-duplex capability of the UECS **402** from the UECS **402**. The base station **122** forwards the full-duplex capability of the

UECS **402** to the coordinating base station **121** that manages resource allocation for the full-duplex communication as described above with respect to FIG. **4**.

(49) FIG. **7** illustrates data and control transactions between devices of a user-equipment-coordination set and a base station in accordance with aspects of user equipment-coordination set full-duplex communication. The UECS includes the DL-coordinating subset **404** (joint-RX UEs **404**), the UL-coordinating subset **406** (joint-TX UEs **406**), an RX-coordinating UE **702**, and a TX-coordinating UE **704**. The roles of the RX-coordinating UE **702** and the TX-coordinating UE **704** can alternatively be performed by a single UE (e.g., the coordinating UE **111**) as illustrated at **706**. The UECS jointly-communicates on behalf of a target UE **708**. Additionally or optionally, the target UE **708** may be included in the DL-coordinating subset **404**, may be included in the UL-coordinating subset **406**, may be the RX-coordinating UE **702**, may be the TX-coordinating UE **704**, or may be the coordinating UE **111**.

(50) At **710**, the base station **121** configures a UECS (e.g., the UECS **402**) including the joint-RX UEs **404**, the joint-TX UEs **406**, the RX-coordinating UE **702**, and the TX-coordinating UE **704**. At **715**, the coordinating UE **111** configures full-duplex communication for the UECS, including selecting the DL-coordinating subset **404** (joint-RX UEs **404**) and the UL-coordinating subset **406** (joint-TX UEs **406**). The coordinating UE **111** also determines if it will assume the roles of the RX-coordinating UE **702** and the TX-coordinating UE **704** or if those roles will be split between two different UEs in the UECS.

(51) At **720**, the coordinating UE **111** transmits an indication that the UECS is capable of full-duplex communication to the base station **121**. The indication can be jointly-transmitted by all or a subset of the UEs in the UECS.

(52) At **725**, the base station **121** transmits a resource grant for the target UE **708** in the UECS. The resource grant indicates downlink resources and uplink resources for full-duplex communication for the target UE **708**. The base station **121** can transmit the resource grant directly to the coordinating UE **111** or to the UECS that jointly-receives the resource grant. When the roles of the RX-coordinating UE **702** and the TX-coordinating UE **704** are performed by different UEs, the coordinating UE **111** forwards the resource grant information to the RX-coordinating UE **702** and the TX-coordinating UE **704** using the local wireless network (not illustrated).

(53) At **730**, the RX-coordinating UE **702** forwards a configuration for joint-reception to the joint-RX UEs **404** using the local wireless network. At **735**, the TX-coordinating UE **704** forwards a configuration for joint-transmission to the joint-TX UEs **406** using the local wireless network. The configuration for joint-reception and/or joint-reception includes, timing advance information, beam configurations, or the like.

(54) At **740**, the UECS conducts full-duplex communication with the base station **121** using the granted resources. The UEs in the DL-coordinating subset **404** (joint-RX UEs **404**) demodulate and sample the downlink signals from the full-duplex communication. At **745**, the UEs in the DL-coordinating subset **404** forward the I/Q samples of the downlink communication to the RX-coordinating UE **702** using the local wireless network.

(55) At **750**, the TX-coordinating UE **704** sends I/Q samples of the uplink data from the full-duplex communication to the RX-coordinating UE **702** using the local wireless network or an internal wired connection for a single coordinating UE **111**. In one alternative, the target UE **708** sends I/Q samples of the uplink data from the full-duplex communication to the RX-coordinating UE **702** using the local wireless network (not illustrated). In another alternative, if the coordinating UE **111** is performing the roles of the RX-coordinating UE **702** and the TX-coordinating UE **704**, the target UE **708** sends I/Q samples of the uplink data from the full-duplex communication to the coordinating UE **111**.

(56) At **755**, the RX-coordinating UE **702** (or the coordinating UE **111**) jointly processes the combined I/Q samples of the downlink communication to provide decoded data. The RX-coordinating UE **702** (or the coordinating UE **111**) uses the I/Q samples of the uplink data to cancel

the undesired crosstalk of the uplink signals from the received downlink signals. At **760**, the RX-coordinating UE **702** (or the coordinating UE **111**) sends the decoded downlink data to the target UE **708**.

Example Methods

(57) FIG. **8** illustrates example method(s) **800** of user equipment-coordination set full-duplex communication as generally related to the coordinating UE of the UECS. At **802**, a coordinating user equipment (e.g., the UE **111**) selects a first subset of UEs (e.g., the DL-coordinating subset **404**) in a UECS (e.g., the UECS **402**) to jointly receive downlink signals. At **804**, the coordinating user equipment selects a second subset of UEs (e.g., the UL-coordinating subset **406**) in the UECS to jointly transmit uplink signals. For example, the coordinating UE **111** evaluates location information associated with UEs in the UECS **402** to select the DL-coordinating subset **404** of UEs and the UL-coordinating subset **406** of UEs to maximize the isolation between the transmission of uplink signals and the reception of downlink signals to facilitate full-duplex communication between the UECS **402** and a base station or ACS.

(58) At **806**, the coordinating UE transmits (or the UECS jointly-transmits) an indication that the UECS is capable of full-duplex communication to a network entity (e.g., the base station **121** or the ACS **602**). For example, the coordinating UE **111** transmits an indication that the UECS **402** is capable of full-duplex communication to the base station **121** or the ACS **602**. The coordinating UE **111** can transmit the indication in a capability information element. The indication includes a further indication of a full-duplex bandwidth for the full-duplex communication.

(59) At **808**, the coordinating UE receives, from the network entity, a resource grant for a target UE in the UECS. For example, the coordinating UE **111** receives (or the UECS jointly-receives) a resource grant that indicates downlink resources and uplink resources for full-duplex communication for a target UE in the UECS **402**.

(60) At **810**, the coordinating UE receives uplink data to transmit to the network entity. For example, the coordinating UE **111** receives uplink data to transmit to the network entity from the target UE or a TX-coordinating UE. The coordinating UE **111** receives the uplink data in the form of I/Q samples using a local wireless connection to the other UEs in the UECS **402**.

(61) At **812**, the coordinating UE receives, from the first subset of UEs, demodulated and sampled downlink data that is received concurrently with joint-transmission of the uplink data by the second subset of UEs. For example, the coordinating UE **111** receives, from the DL-coordinating subset **404** of UEs, demodulated and sampled downlink data that is received by those UEs concurrently with joint-transmission of the uplink data by the UL-coordinating subset **406** of UEs.

(62) At **814**, the coordinating UE combines the samples received from each UE in the first subset of UEs. At **816**, the coordinating UE jointly processes the combined samples to provide decoded data using the received uplink data to cancel crosstalk from uplink signals for the transmitted uplink data to downlink signals for the received downlink data. For example, the coordinating UE **111** combines the samples received from each UE in the DL-coordinating subset **404** of UEs and jointly processes the combined samples to provide decoded data using the received uplink data to cancel crosstalk from uplink signals for the transmitted uplink data to downlink signals for the received downlink data. For example, to cancel crosstalk the coordinating UE reconstructs the transmit interference based on the transmit IQ samples from the UEs that are performing joint-transmission. The coordinating UE then subtracts the reconstructed transmit interference from the received IQ samples of the joint-receiving UEs.

(63) FIG. **9** illustrates example method(s) **900** of user equipment-coordination set full-duplex communication as generally related to a base station communicating with a UECS. At **902**, a base station (e.g., the base station **121**) receives an indication from a user equipment-coordination set (e.g., the UECS **402**) that the UECS is capable of full-duplex communication, the indication including an indication of a full-duplex bandwidth for the full-duplex communication. For example, the base station **121** receives an indication that the UECS **402** is capable of full-duplex

communication. The indication includes a full-duplex bandwidth for the full-duplex communication, and the base station **121** receives the indication in a capability information element.

(64) At **904**, based on the indication that the UECS is capable of full-duplex bandwidth, the base station allocates downlink resources and uplink resources for full-duplex communication with a target UE in the UECS. For example, the base station **121** allocates downlink resources and uplink resources that overlap in time and in frequency for full-duplex communication with a target UE in the UECS **402**.

(65) At **906**, the base station transmits a resource grant to the UECS, the resource grant including an indication of the downlink resources and the uplink resources. For example, the base station **121** transmits a resource grant to the UECS **402**, the resource grant including an indication of the downlink resources and the uplink resources for full-duplex communication.

(66) At **908**, the base station receives uplink signals (e.g., the uplink signals **410**) for uplink data from the UECS using the uplink resources. At **910**, using downlink data that is concurrently transmitted to the UECS with the received uplink signals, the base station processes the received uplink signals to provide decoded data using the downlink data to cancel crosstalk from downlink signals (e.g., the downlink signals **408**) for the transmitted downlink data to the received uplink signals. For example, the base station **121** during full-duplex communication uses downlink data that the base station **121** transmits concurrently with the receiving the uplink signals to cancel crosstalk from downlink signals for the transmitted downlink data to the received uplink signals.

(67) Example methods **800** and **900** are described with reference to FIGS. **8** and **9** in accordance with one or more aspects of user equipment-coordination set full-duplex communication. The order in which the method blocks are described are not intended to be construed as a limitation, and any number of the described method blocks can be skipped, repeated, or combined in any order to implement a method or an alternate method. Generally, any of the components, modules, methods, and operations described herein can be implemented using software, firmware, hardware (e.g., fixed logic circuitry), manual processing, or any combination thereof. Some operations of the example methods may be described in the general context of executable instructions stored on computer-readable storage memory that is local and/or remote to a computer processing system, and implementations can include software applications, programs, functions, and the like.

Alternatively or in addition, any of the functionality described herein can be performed, at least in part, by one or more hardware logic components, such as, and without limitation, Field-programmable Gate Arrays (FPGAs), Application-specific Integrated Circuits (ASICs), Application-specific Standard Products (ASSPs), System-on-a-chip systems (SoCs), Complex Programmable Logic Devices (CPLDs), and the like.

(68) In the following some examples are described:

(69) Example 1: A method performed by a user equipment, UE, configured as a coordinating user equipment for a user equipment-coordination set, UECS, of UEs connected by a local wireless network in a wireless communications network, the method comprising the coordinating user equipment: selecting a first subset of UEs in the UECS to jointly receive downlink signals; selecting a second subset of UEs in the UECS to jointly transmit uplink signals; transmitting an indication that the UECS is capable of full-duplex communication to a network entity; receiving, from the network entity, a resource grant for a target UE in the UECS; receiving uplink data to transmit to the network entity; receiving, from the first subset of UEs, demodulated and sampled downlink data, the demodulated and sampled downlink data jointly received by the first subset of UEs concurrently with joint transmission of modulated and coded uplink data by the second subset of UEs; combining the samples received from each UE in the first subset of UEs; and jointly processing the combined samples to provide decoded data using the received modulated and coded uplink data to cancel crosstalk of uplink signals for the transmitted uplink data from downlink signals for the received downlink data.

(70) Example 2: The method of example 1, wherein the transmitting the indication that the UECS is capable of full-duplex communication comprises: transmitting a UECS Radio Network Temporary Identifier (UECS-RNTI) and/or an indication of an associated full-duplex bandwidth to the network entity.

(71) Example 3: The method of example 1 or example 2, wherein the transmitting the indication that the UECS is capable of full-duplex communication comprises: transmitting the indication that the UECS is capable of full-duplex communication in a capability information element.

(72) Example 4: The method of any of the preceding examples, wherein the UEs included in the first subset of UEs does not overlap with the UEs included in the second subset of UEs.

(73) Example 5: The method of any one of the preceding examples, wherein the selecting the first subset of UEs and selecting the second subset of UEs comprises: selecting the UEs for the first subset of UEs and selecting the second subset of UEs based on location information associated with each respective UE in the UECS.

(74) Example 6: The method of any one of the preceding examples, wherein the coordinating UE coordinates joint-reception of the downlink signals by the first subset of UEs, wherein the coordinating UE coordinates joint-transmission of the uplink signals by the second subset of UEs, and wherein the receiving the uplink data to transmit to the network entity comprises: receiving the uplink data from the target UE over a local wireless connection.

(75) Example 7: The method of any one of the preceding examples, wherein the coordinating UE coordinates joint-reception of the downlink signals by the first subset of UEs, wherein another coordinating UE coordinates joint-transmission of the uplink signals by the second subset of UEs, and wherein the receiving the uplink data to transmit to the network entity comprises: receiving the uplink data from the other coordinating UE.

(76) Example 8: The method of any one of the preceding examples, further comprising the coordinating user equipment: monitoring an indication of performance of the full-duplex communication; based on determining that the indication of the performance is below a threshold value of performance, determining an updated full-duplex bandwidth; and transmitting the updated full-duplex bandwidth to the network entity.

(77) Example 9: The method of example 8, wherein the indication of the performance of the full-duplex communication comprises a ratio of negative acknowledgements, NACKs, to acknowledgments, ACKs, for downlink communications.

(78) Example 10: The method of example 8, wherein the monitoring the indication of performance of the full-duplex communication comprises: measuring a link quality parameter for downlink communications.

(79) Example 11: The method of example 10, wherein the link quality parameter includes: a signal to noise ratio; or signal to noise and interference ratio.

(80) Example 12: The method of any one of the preceding examples, wherein the first subset of UEs includes the coordinating UE, the method further comprising the coordinating UE: receiving downlink signals for the downlink data; demodulating and sampling the downlink signals to produce a set of samples of the downlink signals; and wherein combining the samples received from each UE in the first subset of UEs includes combining the samples with the produced set of samples.

(81) Example 13: The method of any one of the preceding examples, wherein the network entity is a base station.

(82) Example 14: The method of any one of examples 1 to 12, wherein the network entity is an Active Coordination Set, ACS, that includes multiple base stations configured for Coordinated Multipoint Communication, wherein the first subset of UEs in the UECS jointly receives downlink signals from a first subset of base stations in the ACS, and wherein the second subset of UEs in the UECS jointly transmits uplink signals to a second subset of base stations in the ACS.

(83) Example 15: The method of any one of the preceding examples, wherein the resource grant

includes an indication of downlink resources and uplink resources in the same frequency bandwidth and at overlapping times.

(84) Example 16: A user equipment comprising: a radio frequency transceiver; a processor; and memory comprising instructions for a communication manager application that is executable to configure the user equipment to perform any one of the methods of the preceding examples.

(85) Example 17: A method performed by a base station in a wireless communications network, the method comprising the base station: receiving an indication from a user equipment-coordination set, UECS, that the UECS is capable of full-duplex communication; based on the indication that the UECS is capable of full-duplex bandwidth, allocating downlink resources and uplink resources for full-duplex communication with a target user equipment, UE, in the UECS; transmitting a first resource grant to the UECS, the first resource grant including an indication of the downlink resources and the uplink resources; receiving uplink signals for uplink data from the UECS using the uplink resources; and using downlink data that is concurrently transmitted to the UECS with the received uplink signals, processing the received uplink signals to provide decoded data using the downlink data to cancel crosstalk of downlink signals for the transmitted downlink data from received uplink signals.

(86) Example 18: The method of example 17, the method further comprising the base station: receiving an indication of an updated full-duplex bandwidth for the full-duplex communication; based on the indication of the updated full-duplex bandwidth, modifying the allocation of the downlink resources and the uplink resources for the full-duplex communication; and transmitting a second resource grant to the UECS, the second resource grant including an indication of the modified allocation of the downlink resources and the uplink resources.

(87) Example 19: The method of example 17, the method further comprising the base station: receiving an indication of performance of full-duplex communication from the UECS; based on the received indication, modifying the allocation of the downlink resources and the uplink resources for the full-duplex communication such that a portion of the downlink resources and the uplink resources overlap; and transmitting a second resource grant to the UECS, the second resource grant including an indication of the modified allocation of the downlink resources and the uplink resources.

(88) Example 20: The method of any one of examples 17 to 19, the method further comprising the base station: transmitting the downlink data to the UECS concurrently with the receiving uplink signals for uplink data from the UECS.

(89) Example 21: The method of any one of examples 17 to 20, wherein the base station is included in an Active Coordination Set, ACS, the method further comprising the base station: receiving, from another base station in the ACS, the downlink data that is concurrently transmitted to the UECS.

(90) Example 22: The method of any one of examples 17 to 21, wherein the indication that the UECS is capable of full-duplex communication includes an indication of a full-duplex bandwidth for the full-duplex communication.

(91) Example 23: A base station comprising: a wireless transceiver; an inter-base station interface; a processor; and memory comprising instructions for a base station manager application that are executable by the processor to configure the base station to perform any of the methods of example 17 to example 22.

(92) Example 24: A computer-readable medium comprising instructions that, when executed by a processor, cause an apparatus comprising the processor to perform any of the methods of examples 1 to 15 or 17 to 22.

(93) Although aspects of user equipment-coordination set full-duplex communication have been described in language specific to features and/or methods, the subject of the appended claims is not necessarily limited to the specific features or methods described. Rather, the specific features and methods are disclosed as example implementations of user equipment-coordination set full-duplex

communication, and other equivalent features and methods are intended to be within the scope of the appended claims. Further, various different aspects are described, and it is to be appreciated that each described aspect can be implemented independently or in connection with one or more other described aspects.

Claims

1. A method performed by a user equipment (UE) configured as a coordinating user equipment for a user equipment-coordination set (UECS) of UEs connected by a local wireless network in a wireless communications network, the method comprising the coordinating user equipment: selecting a first subset of UEs in the UECS to jointly receive downlink signals; selecting a second subset of UEs in the UECS to jointly transmit uplink signals, the UEs included in the second subset of UEs not overlapping with the UEs included in the first subset of UEs; transmitting an indication that the UECS is capable of full-duplex communication to a network entity; receiving, from the network entity, a resource grant for a target UE for the UECS; receiving uplink data to transmit to the network entity; receiving, from the first subset of UEs, demodulated and sampled downlink data, the demodulated and sampled downlink data jointly received by the first subset of UEs concurrently with joint transmission of modulated and coded uplink data by the second subset of UEs; combining the samples received from each UE in the first subset of UEs; and jointly processing the combined samples to provide decoded data using the received modulated and coded uplink data to cancel crosstalk of uplink signals for the transmitted uplink data from downlink signals for the received downlink data.
2. The method of claim 1, wherein the transmitting of the indication that the UECS is capable of full-duplex communication comprises: transmitting a UECS Radio Network Temporary Identifier (UECS-RNTI) and/or an indication of an associated full-duplex bandwidth to the network entity.
3. The method of claim 1, wherein the transmitting of the indication that the UECS is capable of full-duplex communication comprises: transmitting the indication that the UECS is capable of full-duplex communication in a capability information element.
4. The method of claim 1, wherein the selecting of the first subset of UEs and the selecting of the second subset of UEs comprises: selecting the UEs for the first subset of UEs and selecting the second subset of UEs based on location information associated with each respective UE in the UECS.
5. The method of claim 1, wherein the coordinating UE coordinates joint-reception of the downlink signals by the first subset of UEs, wherein the coordinating UE coordinates joint-transmission of the uplink signals by the second subset of UEs, and wherein the receiving of the uplink data to transmit to the network entity comprises: receiving the uplink data from the target UE over a local wireless connection.
6. The method of claim 1, wherein the coordinating UE coordinates joint-reception of the downlink signals by the first subset of UEs, wherein another coordinating UE coordinates joint-transmission of the uplink signals by the second subset of UEs, and wherein the receiving of the uplink data to transmit to the network entity comprises: receiving the uplink data from the other coordinating UE.
7. The method of claim 1, further comprising the coordinating user equipment: monitoring an indication of performance of the full-duplex communication; based on determining that the indication of the performance is below a threshold value of performance; determining an updated full-duplex bandwidth, and transmitting the updated full-duplex bandwidth to the network entity; or transmitting an indication that the UECS can no longer support full-duplex communication.
8. The method of claim 7, wherein the indication of the performance of the full-duplex communication comprises a ratio of negative acknowledgements (NACKs) to acknowledgments (ACKs) for downlink communications.
9. The method of claim 7, wherein the monitoring of the indication of performance of the full-

duplex communication comprises: measuring a link quality parameter for downlink communications.

10. The method of claim 9, wherein the link quality parameter includes: a signal to noise ratio; or signal to noise and interference ratio.

11. The method of claim 1, wherein the first subset of UEs includes the coordinating UE, the method further comprising the coordinating UE: receiving downlink signals for the downlink data; demodulating and sampling the downlink signals to produce a set of samples of the downlink signals; and wherein combining the samples received from each UE in the first subset of UEs includes combining the samples with the produced set of samples.

12. The method of claim 1, wherein the network entity is a base station.

13. The method of claim 1, wherein the network entity is an Active Coordination Set (ACS) that includes multiple base stations configured for Coordinated Multipoint Communication, wherein the first subset of UEs in the UECS jointly receives downlink signals from a first subset of base stations in the ACS, and wherein the second subset of UEs in the UECS jointly transmits uplink signals to a second subset of base stations in the ACS.

14. The method of claim 1, wherein the resource grant includes an indication of downlink resources and uplink resources in the same frequency bandwidth and at overlapping times.

15. A user equipment (UE) comprising: a radio frequency transceiver; a processor; and memory comprising instructions for a communication manager application that is executable to configure the user equipment to: select a first subset of UEs in a user equipment-coordination set (UECS) to jointly receive downlink signals; select a second subset of UEs in the UECS to jointly transmit uplink signals, the UEs included in the second subset of UEs not overlapping with the UEs included in the first subset of UEs; transmit an indication that the UECS is capable of full-duplex communication to a network entity; receive, from the network entity, a resource grant for a target UE in the UECS; receive uplink data to transmit to the network entity; receive, from the first subset of UEs, demodulated and sampled downlink data, the demodulated and sampled downlink data jointly received by the first subset of UEs concurrently with joint transmission of modulated and coded uplink data by the second subset of UEs; combine the samples received from each UE in the first subset of UEs; and jointly process the combined samples to provide decoded data using the received modulated and coded uplink data to cancel crosstalk of uplink signals for the transmitted uplink data from downlink signals for the received downlink data.

16. A method performed by a base station in a wireless communications network, the method comprising the base station: receiving an indication from a user equipment-coordination set (UECS) that the UECS is capable of full-duplex communication, the UECS comprising a first subset of UEs for jointly receiving downlink signals and a second subset of UEs for jointly transmitting uplink signals, the UEs included in the second subset of UEs not overlapping with the UEs included in the first subset of UEs; based on the indication that the UECS is capable of full-duplex bandwidth, allocating downlink resources and uplink resources for full-duplex communication with a target user equipment (UE) in the UECS; transmitting a first resource grant to the UECS, the first resource grant including an indication of the downlink resources and the uplink resources; receiving, from the second subset of UEs in the UECS, uplink signals for uplink data using the uplink resources; and using downlink data that is concurrently transmitted to the first subset of UEs in the UECS with the received uplink signals, processing the received uplink signals to provide decoded data using the downlink data to cancel crosstalk of downlink signals for the transmitted downlink data from received uplink signals.

17. The method of claim 16, the method further comprising the base station: receiving an indication of an updated full-duplex bandwidth for the full-duplex communication; based on the indication of the updated full-duplex bandwidth, modifying the allocation of the downlink resources and the uplink resources for the full-duplex communication; and transmitting a second resource grant to the UECS, the second resource grant including an indication of the modified allocation of the downlink

resources and the uplink resources.

18. The method of claim 16, the method further comprising the base station: receiving an indication of performance of full-duplex communication from the UECS; based on the received indication, modifying the allocation of the downlink resources and the uplink resources for the full-duplex communication such that a portion of the downlink resources and the uplink resources overlap; and transmitting a second resource grant to the UECS, the second resource grant including an indication of the modified allocation of the downlink resources and the uplink resources.

19. The method of claim 16, the method further comprising the base station: transmitting the downlink data to the UECS concurrently within the same frequency bandwidth with the receiving uplink signals for uplink data from the UECS.

20. The method of claim 16, wherein the base station is included in an Active Coordination Set (ACS) the method further comprising the base station: receiving, from another base station in the ACS, the downlink data that is concurrently transmitted to the UECS.

21. The method of claim 16, wherein the indication that the UECS is capable of full-duplex communication includes an indication of a full-duplex bandwidth for the full-duplex communication.

22. A base station comprising: a wireless transceiver; an inter-base station interface; a processor; and memory comprising instructions for a base station manager application that are executable by the processor to configure the base station to: receive an indication from a user equipment-coordination set (UECS) that the UECS is capable of full-duplex communication, the UECS comprising a first subset of UEs for jointly receiving downlink signals and a second subset of UEs for jointly transmitting uplink signals, the UEs included in the second subset of UEs not overlapping with the UEs included in the first subset of UEs; based on the indication that the UECS is capable of full-duplex bandwidth, allocate downlink resources and uplink resources for full-duplex communication with a target user equipment (UE) in the UECS; transmit a first resource grant to the UECS, the first resource grant including an indication of the downlink resources and the uplink resources; receive, from the second subset of UEs in the UECS, uplink signals for uplink data using the uplink resources; and using downlink data that is concurrently transmitted to the first subset of UEs in the UECS with the received uplink signals, process the received uplink signals to provide decoded data using the downlink data to cancel crosstalk of downlink signals for the transmitted downlink data from received uplink signals.
