

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent	12416985
Kind Code	B2
Date of Patent	September 16, 2025
Inventor(s)	Liu; Siyuan et al.

Terminal device and display screen thereof, and preparation method for display screen

Abstract

The present application relates to a terminal device and a display screen thereof, and a preparation method for the display screen, wherein the display screen includes a cover plate layer, a touch layer, a polarizing layer, an encapsulation layer, a pixel layer and a circuit driving layer from top to bottom. In particular, the display screen further includes a microlens layer formed above the pixel layer, wherein the microlens layer corresponds to each gap between pixels in the pixel layer, and is used to converge light to each of the gaps before the light passes through the pixel layer via the gaps so as to increase the light transmittance of the display screen.

Inventors:	Liu; Siyuan (Zhejiang, CN), Jing; Liao (Zhejiang, CN), Wu; Xudong (Zhejiang, CN)
Applicant:	NINGBO SUNNY OPOTECH CO., LTD. (Zhejiang, CN)
Family ID:	1000008819623
Assignee:	NINGBO SUNNY OPOTECH CO., LTD. (Zhejiang, CN)
Appl. No.:	17/599268
Filed (or PCT Filed):	March 12, 2020
PCT No.:	PCT/CN2020/078952
PCT Pub. No.:	WO2020/192436
PCT Pub. Date:	October 01, 2020

Prior Publication Data

Document Identifier	Publication Date
US 20220190294 A1	Jun. 16, 2022

Foreign Application Priority Data

CN	201910243137.2	Mar. 28, 2019
CN	201920412018.0	Mar. 28, 2019

Publication Classification

Int. Cl.: G06F3/041 (20060101); H01L25/18 (20230101); H04M1/02 (20060101); H10K50/844 (20230101); H10K59/12 (20230101); H10K59/17 (20230101); H10K59/65 (20230101); H10K59/80 (20230101); H10K71/00 (20230101)

U.S. Cl.:

CPC G06F3/0412 (20130101); H10K50/844 (20230201); H10K59/65 (20230201); H10K59/879 (20230201); H10K59/8791 (20230201); H10K71/00 (20230201); H01L25/18 (20130101); H04M1/0266 (20130101); H10K59/12 (20230201); H10K59/17 (20230201); H10K59/873 (20230201)

Field of Classification Search

CPC: H10K (50/844); H10K (71/00); H10K (59/12); H10K (59/17); H10K (59/65); H10K (59/879); H10K (59/8791); H10K (59/873); G06F (3/0412); G06F (2203/04103); H01L (25/18); H04M (1/0266)

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
9887359	12/2017	Ciou	N/A	H10K 71/621
10872222	12/2019	Gao et al.	N/A	N/A
2010/0301367	12/2009	Nakamura	257/E33.059	H01L 33/507
2014/0085865	12/2013	Yun et al.	N/A	N/A
2015/0380466	12/2014	Koo et al.	N/A	N/A
2017/0251137	12/2016	Evans, V et al.	N/A	N/A
2018/0097204	12/2017	Ivan	N/A	H10K 59/8792
2019/0006626	12/2018	Kim et al.	N/A	N/A
2019/0285950	12/2018	Liu	N/A	H05K 3/3431
2019/0335553	12/2018	Ahmed	N/A	G09G 3/32

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
107346152	12/2016	CN	N/A

107515435	12/2016	CN	N/A
108227978	12/2017	CN	N/A
108650443	12/2017	CN	N/A
108682295	12/2017	CN	N/A
108732801	12/2017	CN	N/A
108803146	12/2017	CN	N/A
108803146	12/2017	CN	G02F 1/133528
209928406	12/2019	CN	N/A
3 016 166	12/2015	EP	N/A
3 333 682	12/2021	EP	N/A
2014-063163	12/2013	JP	N/A
10-2016-0001260	12/2015	KR	N/A
10-2019-0003216	12/2018	KR	N/A
2007/138543	12/2006	WO	N/A

OTHER PUBLICATIONS

English translation of CN 198893146 (Year: 2018). cited by examiner

International Search Report issued Jun. 11, 2020, in International (PCT) Application No. PCT/CN2020/078952, with English translation. cited by applicant

Extended European Search Report issued May 16, 2022 in European Patent Application No. 20776741.9. cited by applicant

Office Action issued Mar. 28, 2022 in Indian Patent Application No. 202117048220. cited by applicant

Abrahamson, Joel T. et al., “Optically Clear Adhesives for OLED”, Selection of our books indexed in the Book Citation Index in Web of Science™ Core Collection (BKCI), Aug. 23, 2019, pp. 1-27, XP055918160. cited by applicant

Primary Examiner: Partridge; William B

Assistant Examiner: Sedorook; David Paul

Attorney, Agent or Firm: Wenderoth, Lind & Ponack, L.L.P.

Background/Summary

FIELD OF THE INVENTION

(1) The present application relates to a terminal device, and in particular, to a terminal device having a full screen and a display screen thereof, and a preparation method of the display screen.

BACKGROUND OF THE INVENTION

(2) In recent years, full-screen terminal devices (for example, full-screen mobile phones) have gradually become popular among users. The existing full-screen terminal device refers to an ultra-large-screen terminal device of which a screen exceeds a preset percentage (for example, 90%) of a front face of the device, and does not truly achieve a 100% screen-to-body ratio.

(3) At present, in the technical solutions of increasing the screen-to-body ratio, a camera module on the same side of the terminal device together with the screen is the biggest obstacle. However, a camera function is often an indispensable functional requirement for the terminal device. Therefore, it is necessary to optimize a structural configuration of the screen and the camera module so as to increase the screen-to-body ratio of the terminal device.

SUMMARY OF THE INVENTION

(4) The present application is mainly directed to provide a terminal device and a display screen thereof, and a preparation method of the display screen, wherein the display screen has relatively high light transmittance, so that on one hand, a camera module provided below the display screen can collect sufficient amount of imaging light, and on the other hand, a screen-to-body ratio of the terminal device can be increased.

(5) The present application is further directed to provide a terminal device and a display screen thereof, and a preparation method of the display screen, wherein a camera module is configured as an under-screen camera module, which, together with the display screen, is mounted at different height positions of the terminal device, and thus, the camera module is free from being an obstacle to increasing a screen-to-body ratio.

(6) The present application is further directed to provide a terminal device and a display screen thereof, and a preparation method of the display screen, wherein the display screen includes a microlens layer provided above a pixel layer, so that light entering the display screen is converged to gaps between various pixels in the pixel layer through the microlens layer, and by this way, the light transmittance of the display screen is improved.

(7) The present application is further directed to provide a terminal device and a display screen thereof, and a preparation method of the display screen, wherein the display screen of the present application does not require a sharp adjustment to the existing structure of the existing display screen, and only one microlens layer corresponding to gaps between various pixels of a pixel layer needs to be additionally provided above the pixel layer of the display screen.

(8) The present application is further directed to provide a terminal device and a display screen thereof, and a preparation method of the display screen, wherein a refractive index of a material for forming a microlens layer is higher than that of a material for forming an encapsulation layer, thereby improving the light transmittance of the display screen.

(9) Other advantages and features of the present application will become obvious through the following description, and can be implemented by means and combinations particularly pointed out in the claims.

(10) To realize at least one of the above objectives or advantages, the present application provides a display screen, including: a cover plate layer, a touch layer, a polarizing layer, an encapsulation layer, a pixel layer, and a circuit driving layer from top to bottom, wherein the circuit driving layer is formed on a bottom side of the pixel layer, and is electrically connected to the pixel layer to drive the pixel layer to operate; the encapsulation layer is formed on a top side of the pixel layer to encapsulate the pixel layer; and the pixel layer includes pixels distributed in an array, gaps are reserved between various pixels to allow light passing through the cover plate layer, the touch layer, the polarizing layer and the encapsulation layer in sequence to pass through the pixel layer via the gaps; wherein, the display screen further includes a microlens layer provided above the pixel layer, and the microlens layer corresponds to each gap between the pixels, and is used to converge the light to each gap before the light passes through the pixel layer via the gaps so as to increase the light transmittance of the display screen.

(11) In an embodiment of the present application, the microlens layer includes microlens units distributed in an array, wherein each microlens unit respectively corresponds to each gap.

(12) In an embodiment of the present application, the microlens layer is integrally formed in each gap between the pixels in the pixel layer, and the encapsulation layer is integrally formed on the microlens layer and the pixel layer to encapsulate the pixel layer and the microlens layer.

(13) In an embodiment of the present application, the microlens layer is integrally formed on a top surface of the encapsulation layer.

(14) In an embodiment of the present application, the microlens layer is integrally formed on the top surface of the encapsulation layer in a recessed manner.

(15) In an embodiment of the present application, a height size of the microlens unit is smaller than

or equal to that of the encapsulation layer.

(16) In an embodiment of the present application, a horizontal size of the microlens unit is larger than a size of the gap.

(17) In an embodiment of the present application, a longitudinal size of the microlens unit is larger than or equal to a size of a gap between adjacent pixels.

(18) In an embodiment of the present application, the material for forming the encapsulation layer is a light-transmissive rigid material.

(19) In an embodiment of the present application, the material for forming the encapsulation layer is a light-transmissive flexible material.

(20) In an embodiment of the present application, the display screen further includes a back plate layer having an opening hole, and the opening hole corresponds to the gaps between adjacent pixels in the pixel layer.

(21) According to another aspect of the present application, the present application further provides a preparation method of a display screen, including:

(22) forming a microlens layer on a pixel layer of the display screen, wherein the microlens layer corresponds to gaps between various pixels in the pixel layer, and a circuit driving layer is provided on a bottom side of the pixel layer, and the circuit driving layer is electrically connected to the pixel layer to drive the pixel layer to operate; and forming an encapsulation layer on the microlens layer and the pixel layer to encapsulate the microlens layer and the pixel layer by the encapsulation layer, and the encapsulation layer is further provided thereon with a polarizing layer, a touch layer and a cover plate layer in sequence.

(23) In an embodiment of the present application, the microlens layer is integrally formed in the gaps between various pixels in the pixel layer.

(24) In an embodiment of the present application, the encapsulation layer is integrally formed on the microlens layer and the pixel layer by a deposition process.

(25) In an embodiment of the present application, a refractive index of a material for forming the microlens layer is higher than that of a material for forming the encapsulation layer.

(26) According to yet another aspect of the present application, the present application provides a preparation method of a display screen, including:

(27) integrally forming a microlens layer on an encapsulation layer;

(28) providing the encapsulation layer above a pixel layer, wherein the microlens layer corresponds to gaps between various pixels in the pixel layer, and a circuit driving layer is provided on a bottom side of the pixel layer, and the circuit driving layer is electrically connected to the pixel layer to drive the pixel layer to operate; and

(29) providing a polarizing layer, a touch layer and a cover plate layer in sequence on the encapsulation layer.

(30) In an embodiment of the present application, the microlens layer is integrally formed on a top surface of the encapsulation layer.

(31) In an embodiment of the present application, the microlens layer is integrally formed on the top surface of the encapsulation layer in a recessed manner.

(32) According to another aspect of the present application, the present application further provides a terminal device, including: a terminal main body, a camera module, and the above display screen, wherein the display screen is mounted on the terminal main body, and the camera module is provided on a bottom side of the display screen, so that the camera module can receive imaging light that passes through the cover plate layer, the touch layer, the polarizing layer, the encapsulation layer, the microlens layer, the gaps of the pixel layer, and the circuit driving layer of the display screen in sequence.

(33) In an embodiment of the present application, the camera module is mounted in the opening hole of the back plate layer located at the bottom of the display screen.

(34) The further objectives and advantages of the present application will become more fully

apparent from the understanding of the following description and the accompanying drawings. (35) These and other objectives, characteristics, and advantages of the present application will become more fully apparent from the following detailed description, the accompanying drawings and the claims.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

- (1) FIG. 1 is a schematic structural diagram of a display screen used in an existing terminal device;
- (2) FIG. 2 is a schematic structural diagram of a display screen according to an embodiment of the present application;
- (3) FIG. 3A is a variant implementation mode of the display screen according to an embodiment of the present application;
- (4) FIG. 3B is a schematic diagram of a preparation process of the display screen according to an embodiment of the present application;
- (5) FIG. 3C is a schematic diagram of a preparation process of the display screen according to an embodiment of the present application;
- (6) FIG. 3D is a schematic diagram of a preparation process of the display screen according to an embodiment of the present application;
- (7) FIG. 3E is a schematic diagram of a preparation process of the display screen according to an embodiment of the present application;
- (8) FIG. 3F is a schematic diagram of a preparation process of the display screen according to an embodiment of the present application;
- (9) FIG. 3G is a schematic diagram of a preparation process of the display screen according to an embodiment of the present application;
- (10) FIG. 4A is a schematic diagram of a microlens array in the display screen according to an embodiment of the present application;
- (11) FIG. 4B is another schematic diagram of the microlens array in the display screen according to an embodiment of the present application;
- (12) FIG. 5 is another variant implementation mode of the display screen according to an embodiment of the present application;
- (13) FIG. 6A is another variant implementation mode of the display screen according to an embodiment of the present application;
- (14) FIG. 6B is another variant implementation mode of the display screen according to an embodiment of the present application;
- (15) FIG. 7 is yet another variant implementation mode of the display screen according to an embodiment of the present application;
- (16) FIG. 8A is yet another variant implementation mode of the display screen according to an embodiment of the present application;
- (17) FIG. 8B is another variant implementation mode of the display screen according to an embodiment of the present application;
- (18) FIG. 9 is yet another variant implementation mode of the display screen according to an embodiment of the present application;
- (19) FIG. 10 is a schematic diagram of a preparation process of the display screen according to an embodiment of the present application;
- (20) FIG. 11 is a schematic diagram of another preparation process of the display screen according to an embodiment of the present application;
- (21) FIG. 12 is a schematic diagram of yet another preparation process of the display screen according to an embodiment of the present application;

- (22) FIG. 13 is a schematic diagram of yet another preparation process of the display screen according to an embodiment of the present application;
- (23) FIG. 14 is a schematic diagram of yet another preparation process of the display screen according to an embodiment of the present application;
- (24) FIG. 15 is a schematic diagram of yet another preparation process of the display screen according to an embodiment of the present application;
- (25) FIG. 16 is a schematic diagram of yet another preparation process of the display screen according to an embodiment of the present application;
- (26) FIG. 17 is a specific example of a terminal device according to an embodiment of the present application;
- (27) FIG. 18 is a schematic diagram of an imaging path of a camera module in the terminal device according to an embodiment of the present application;
- (28) FIG. 19 is another schematic diagram of the terminal device according to an embodiment of the present application;
- (29) FIG. 20 is yet another schematic diagram of the terminal device according to an embodiment of the application;
- (30) FIG. 21 is a specific example of a camera module according to an embodiment of the present application;
- (31) FIG. 22 is another specific example of a camera module according to an embodiment of the application;
- (32) FIG. 23 is yet another specific example of a camera module according to an embodiment of the present application;
- (33) FIG. 24 is yet another specific example of a camera module according to an embodiment of the present application;
- (34) FIG. 25 is yet another specific example of a camera module according to an embodiment of the present application;
- (35) FIG. 26 is yet another specific example of a camera module according to an embodiment of the present application;
- (36) FIG. 27 is yet another specific example of a camera module according to an embodiment of the present application;
- (37) FIG. 28 is yet another specific example of a camera module according to an embodiment of the present application;
- (38) FIG. 29 is yet another specific example of a camera module according to an embodiment of the present application;
- (39) FIG. 30 is yet another specific example of a camera module according to an embodiment of the present application;
- (40) FIG. 31 is yet another specific example of a camera module according to an embodiment of the present application;
- (41) FIG. 32 is yet another specific example of a camera module according to an embodiment of the present application;
- (42) FIG. 33 is yet another specific example of a camera module according to an embodiment of the present application;
- (43) FIG. 34 is a schematic diagram of an existing molding process-based camera module;
- (44) FIG. 35 is a specific example of a photosensitive chip of the camera module; and
- (45) FIG. 36 is another specific example of the photosensitive chip of the camera module.

DETAILED DESCRIPTION OF THE INVENTION

(46) The following description is used to disclose the present application to enable those skilled in the art to implement the present application. The preferred embodiments in the following description are by way of examples only, and other obvious variations will occur to those skilled in the art. The basic principles of the present application as defined in the following description can

be applied to other embodiments, variations, improvements, equivalents, and other technical solutions without departing from the spirit and scope of the present application.

(47) It should be understood by those skilled in the art that in the disclosure of the present application, the orientation or positional relationship indicated by terms “longitudinal”, “transverse”, “upper”, “lower”, “front”, “back”, “left”, “right”, “vertical”, “horizontal”, “top”, “bottom”, “inside”, “outside”, etc. is based on the orientation or positional relationship shown in the drawings, which is merely for the convenience of describing the present application and for the simplification of the description, and not to indicate or imply that the apparatus or element referred to must have a specific orientation, or be constructed and operated in a specific orientation.

Therefore, the above terms shall not be construed as a limitation of the present application.

(48) It can be understood that the term “a” is understood to mean “at least one” or “one or more”, that is, in an embodiment, the number of an element can be one, and in another embodiment, the number of the elements can be plural, and the term “a” cannot be construed as limiting the quantity.

(49) Although ordinal numbers such as “first” and “second” will be used to describe various components, those components are not limited herein. These terms are only used to distinguish a component from another component. For example, a first component may be referred to as a second component, and similarly, the second component may also be referred to as the first component without departing from the teaching of the inventive concept. The term “and/or” as used herein includes any and all combinations of one or more of the associated items that are listed.

(50) Terms used herein are merely for the purpose of describing various embodiments, rather than limitation. As used herein, the singular form is intended to also include the plural form, unless the context clearly indicates an exception. In addition, it will be understood that the terms “include” and/or “have” when used in the specification, specify the presence of the described features, numbers, steps, operations, components, elements, or combinations thereof, and do not exclude the presence or addition of one or more other features, number, steps, operations, components, elements, or combinations thereof.

(51) The terms used herein, including technical and scientific terms, have the same meanings as those commonly understood by those skilled in the art, as long as the terms are not defined differently. It should be understood that terms defined in commonly used dictionaries have the same meanings as the meanings of the terms in the prior art.

(52) The present invention will be further described below in detail with reference to the drawings and specific embodiments.

(53) Application Overview

(54) As described above, in the technical solutions of increasing a screen-to-body ratio, a camera module provided on the same side of a terminal device together with a screen is the biggest obstacle. To truly realize a full screen and reduce the impact of the camera module on the screen-to-body ratio, an existing technical solution is to use a retractable camera module to hide and use the camera module. Specifically, when shooting is required, the camera module is extended out of a housing of the terminal device for shooting; and after the shooting is completed, the camera module is retracted into the housing of the terminal device.

(55) However, the technical solution has many drawbacks in practical applications. Firstly, the camera module is vulnerable to damage caused by external impact in the process of continuously retracting into and/or extending out of the housing of the terminal device. Secondly, once damaged, the camera module and a retractable mechanism are difficult to replace.

(56) In recent years, a technical idea of an under-screen camera module has been proposed, that is, the camera module is provided below the display screen. However, since the camera module is provided below the display screen, it cannot collect sufficient amount of imaging light from the outside, which makes imaging function of the camera module difficult to achieve.

(57) In detail, FIG. 1 is a schematic structural diagram of a display screen used in an existing terminal device. As shown in FIG. 1, the display screen is an OLED display screen, which includes

a cover plate layer **21P**, a touch layer **22P**, a polarizing layer **23P**, an encapsulation layer **24P**, a pixel layer **25P**, a circuit driving layer **26P**, and a back plate layer **27P** from top to bottom. Herein, the cover plate layer **21P** is bound to a top side of the touch layer **22P** by an adhesive; the polarizing layer **23P** is provided on a bottom side of the touch layer **22P**; the encapsulation layer **24P** is provided on a bottom side of the polarizing layer **23P** to encapsulate the pixel layer **25P**, so that the pixel layer **25P** is in a sealed environment, thereby protecting an organic material in the pixel layer **25P** from being polluted by the outside or volatilizing; the circuit driving layer **26P** is provided on a bottom side of the pixel layer **25P** to drive the pixel layer **25P** to operate, so that the display screen can display images; and moreover, the back plate layer **27P** is provided on a bottom side of the circuit driving layer **26P** to enhance the structural strength of the display screen.

(58) In other words, when the camera module is provided below the display screen, imaging light from the outside needs to pass through the cover plate layer **21P**, the touch layer **22P**, the polarizing layer **23P**, the encapsulation layer **24P**, the pixel layer **25P**, the circuit driving layer **26P**, and the back plate layer **27P** of the display screen in sequence, and thus can be sensed by the camera module provided below the display screen. Those skilled in the art should know that the light transmittance of the existing display screen is usually low, and the main reason is that the pixel layer **25P** has a relatively high light resistance rate, and most of imaging light passes through the pixel layer **25P** via gaps between pixels.

(59) Theoretically, in order to improve the light transmittance of the existing display screen, a size proportion of the gaps between various pixels in the pixel layer can be increased, for example, a size of a unit pixel can be reduced or a size of the gap between the pixels can be increased. However, reducing the size of a unit pixel will reduce a luminous intensity of the pixel and thus lead to shortening of the service life of the pixel, and enlarging the gaps between the pixels will directly reduce the screen resolution. In other words, the technical solution of increasing the size proportion of the gaps between the pixels will cause damage to the performance of the display screen, which is not advantageous for the development of the display technology.

(60) In view of the above technical problems, the basic idea of the present application is to provide a microlens layer on the pixel layer of the display screen so as to converge the imaging light that passes through the cover layer, the touch layer, the polarizing layer and the encapsulation layer in sequence to the gaps between various pixels in the pixel layer by the microlens layer. By this way, the light transmittance of the display screen is increased, so that the camera module provided below the display screen can collect sufficient amount of imaging light for imaging.

(61) In view of this, the present application proposes a terminal device, including: a terminal main body, a camera module, and a display screen, wherein the display screen is mounted on the terminal main body, and the camera module is provided on a bottom side of the display screen, and the display screen includes a cover plate layer, a touch layer, a polarizing layer, an encapsulation layer, a pixel layer, and a circuit driving layer from top to bottom. Wherein, the circuit driving layer is formed on a bottom side of the pixel layer, and is electrically connected to the pixel layer to drive the pixel layer to operate; the encapsulation layer is formed on a top side of the pixel layer to encapsulate the pixel layer; and the pixel layer includes pixels distributed in an array, gaps are reserved between various pixels to allow light passing through the cover plate layer, the touch layer, the polarizing layer and the encapsulation layer in sequence to pass through the pixel layer via the gaps. The display screen further includes a microlens layer, wherein the microlens layer is formed inside the encapsulation layer, and the microlens layer corresponds to the gaps between various pixels, and is used to converge light to the gaps before the light passes through the pixel layer via the gaps, so that larger amount of light can pass through the pixel layer via the gaps between various pixels in the pixel layer, and pass through the circuit driving layer to reach the camera module. In other words, by providing the microlens layer in the display screen, the light transmittance of the display screen is improved, so that when the camera module is provided below the display screen, the camera module can still collect sufficient amount of imaging light for

imaging. That is, by the optimized display screen, the technical solution of the under-screen camera module can be implemented so as to truly realize the full-screen design of a terminal device.

(62) After introducing the basic principles of the present application, various non-limiting embodiments of the present application will be described in detail below with reference to the accompanying drawings.

(63) Exemplary Display Screen

(64) FIG. 2 is a schematic structural diagram of a display screen according to an embodiment of the present application. As shown in FIG. 2, the display screen **20** used for realizing a full-screen configuration of a terminal device (for example, a smart phone) according to the embodiment of the present application includes a cover plate layer **21**, a touch layer **22**, a polarizing layer **23**, an encapsulation layer **24**, a pixel layer **25**, and a circuit driving layer **26** which are provided from top to bottom. Wherein, the circuit driving layer **26** is formed on a bottom side of the pixel layer **25**, and is electrically connected to the pixel layer **25** to drive the pixel layer **25** to operate; the encapsulation layer **24** is formed on a top side of the pixel layer **25** to encapsulate the pixel layer **25**; and the pixel layer **25** includes pixels **251** distributed in an array, gaps **250** are reserved between various pixels **251** to allow light passing through the cover plate layer **21**, the touch layer **22**, the polarizing layer **23** and the encapsulation layer **24** in sequence to pass through the pixel layer **25** via the gaps **250**.

(65) Particularly, the display screen **20** further includes a microlens layer **28** provided above the pixel layer **25**, wherein the microlens layer **28** corresponds to each gap **250** between the pixels **251** in the pixel layer **25**, and is used to converge light to each gap **250** before the light passes through the pixel layer **25** via the gaps **250**. By this way, the overall light transmittance of the display screen **20** can be efficiently increased.

(66) As shown in FIG. 2, in the embodiment of the present application, the display screen **20** is implemented as an OLED (Organic Light-emitting Diode) display screen **20**. Those skilled in the art should know that the OLED display screen **20** has the advantages of self-luminescence, wide viewing angle, high contrast, low power consumption, high response speed, full color, etc.

However, the light transmittance of the existing OLED display screen **20** is generally not high.

(67) A “layer-by-layer” analysis of the existing OLED display screen **20** will be made below to explain the reasons for the low light transmittance of the existing OLED display screen. As previously described, the existing OLED display screen **20** includes a cover plate layer **21P**, a touch layer **22P**, a polarizing layer **23P**, an encapsulation layer **24P**, a pixel layer **25P**, a circuit driving layer **26P**, and a back plate layer **27P** from top to bottom.

(68) Firstly, the cover plate layer **21P** is usually implemented as a glass layer, and it is the topmost layer of the display screen, and is used to protect layer structures located below the cover plate layer **21P**. It should be understood that the glass layer is made of a glass material which is a material with high light transmittance. That is, the cover plate layer **21P** does not adversely affect the light transmittance of the display screen.

(69) A layer structure located below the cover plate layer **21P** is the touch layer **22P**, and usually they are bound together by an adhesive. Those skilled in the art should know that the touch layer **22P** is an indispensable configuration for realizing a touch function of the display screen. In other words, the influence of the touch layer **22P** on the light transmittance of the display screen is almost inevitable.

(70) A layer structure located below the touch layer **22P** is the polarizing layer **23P**, which is usually implemented as a circular polarizer or the like. It should be understood that the polarizing layer **23P** such as a circular polarizer is an optical element, and has relatively high light transmittance. Therefore, the polarizing layer **23P** does not greatly affect the light transmittance of the display screen.

(71) A layer structure located below the polarizing layer **23P** is the encapsulation layer **24P**, which is used to encapsulate the pixel layer **25P** located below the encapsulation layer **24P**, so that the

pixel layer **25P** is in a sealed environment, thereby protecting an organic material in the pixel layer **25P** from being polluted by the outside or volatilizing. Specifically, the encapsulation layer **24P** has two types, wherein when the display screen is a rigid screen, the encapsulation layer **24P** is made of a light-transmissive rigid material such as glass and plastic; and when the display screen is a flexible screen, the encapsulation layer **24P** is made of a light-transmissive flexible material such as a PI film (Polyimide Film). It should be observed that regardless of a rigid screen or a flexible screen, the encapsulation layer **24P** is made of a light-transmissive material, and thus it does not greatly affect the overall light transmittance of the display screen.

(72) A layer structure covered by the encapsulation layer **24P** and located below the encapsulation layer **24P** is the pixel layer **25P**. For the OLED display screen, pixel units in the pixel layer **25** are implemented as OLEDs (Organic Light-emitting Diodes). Those skilled in the art should know that the organic light-emitting diode has a high light resistance rate, that is, light passing through the cover plate layer **21P**, the touch layer **22P**, the polarizing layer **23P**, and the encapsulation layer **24P** and reaching the pixel layer **25** is difficult to pass through the organic light-emitting diode to reach the other side of the pixel layer **25**. Accordingly, this part of light only can pass through the pixel layer **25P** by means of gaps between various pixels. That is, the pixel **25P** has a light transmitting area and a non-light transmitting area, wherein the light transmitting area is defined by the gaps between the pixels, and the non-light transmitting area is defined by the pixels. However, a ratio of the gaps between the pixels to the total area of the pixel layer **25P** is relatively small, and therefore, a large amount of light is blocked by the pixel layer **25P**, resulting in relatively low overall light transmittance of the display screen.

(73) A layer structure located below the pixel layer **25P** is the circuit driving layer **26P**, which is electrically connected to the pixel layer **25P** to drive the pixel layer **25P** to operate. The circuit driving layer **26P** includes a driving circuit and a packaging layer for encapsulating the driving circuit, wherein the packaging layer is made of a material with relatively high light transmittance, and thus it does not greatly affect the overall light transmittance of the display screen. However, improper arrangement of the driving circuit will affect the transmission of light. Specifically, if electronic elements of the driving circuit correspond to the gaps between the pixels, this part of the driving circuit will adversely affect light passing through the display screen; and if the elements of the driving circuit are located below the pixels, this part of the driving circuit will not affect the transmission of light.

(74) A layer structure located below the circuit driving layer **26P** is the back plate layer, which is mainly used to enhance the overall structural strength of the display screen. When the display screen is an OLED display screen, the light transmittance of the back plate layer is not low, and when the display screen is an LCD display screen, the back plate layer is used to provide a light source, and the light transmittance is relatively low.

(75) In conclusion, the reasons for the low overall light transmittance of the existing OLED display screens are that: first, the proportion of the light transmitting area of the pixel layer **25P** is relatively low, that is, the proportion of the gaps between the pixels is relatively low, so that only small amount of light can pass through the pixel layer **25P** via the gaps between the pixels; second, a part of the driving circuit (when the elements of the driving circuit correspond to the gaps between the pixels) in the circuit driving layer **26P** will affect the light transmittance of the display screen.

(76) Accordingly, in the embodiment of the present application, the display screen **20** is provided with a microlens layer **28** which is provided above the pixel layer **25** and corresponds to each gap **250** between the pixels **251** in the pixel layer **25**. The microlens layer **28** has a light converging function and is used to converge light to each gap **250** between the pixels **251**, so that larger amount of light can effectively pass through the pixel layer **25** via the gaps **250** between the pixels **251** without changing the size proportion of the gaps **250** between the pixels.

(77) Further, the back plate layer is an unnecessary functional layer of the display screen **20**, and therefore, in the embodiment of the present application, the back plate layer **27P** can be directly

omitted. Or, an opening hole **270** is provided at a position where the back plate layer **27** needs to transmit light.

(78) Through the above optimization, the overall light transmittance of the display screen **20** can be effectively increased, so that light from the outside can pass through the cover plate layer **21**, the touch layer **22**, the polarizing layer **23**, the encapsulation layer **24**, the microlens layer **28** and the circuit driving layer **26** in sequence from one side (referred to as a front face) of the display screen **20** to reach the other side (referred to as a rear face) of the display screen **20**.

(79) FIG. 3A is a variant implementation mode of the display screen **20** according to an embodiment of the present application. As shown in FIG. 3, in the variant implementation mode, the display screen further includes a back plate layer **27** supporting a bottom side of the circuit driving layer **26** so as to enhance the structural strength of the display screen **20** through the back plate layer **27**. Particularly, at least one opening hole **270** is provided at a position where the display screen **20** needs to transmit light of the back plate layer **27**, wherein the opening hole **270** corresponds to the gaps **250** between the pixels **251** in the pixel layer **25** to allow light passing through the pixel layer **25** via the gaps **250** of the pixel layer **25** to reach the rear face of the display screen via the opening hole **270**.

(80) It is worthwhile to note that in the embodiment of the present application, optionally, the opening hole **270** has a size corresponding to a camera module mounted below the display screen **20**, and thus, the opening hole **270** itself can serve as a reference hole for mounting and positioning the camera module, which is advantageous for installation and calibration of the camera module. Moreover, when the camera module is mounted in the opening hole **270**, light passing through the display screen **20** via the opening hole **270** can directly enter the camera module to perform an imaging reaction.

(81) To further improve the light transmittance of the display screen **20**, in the embodiment of the present application, the circuit driving layer **26** can also be optimized. Specifically, the arrangement of the driving circuit in the circuit driving layer **26** is adjusted to: prevent the elements in the driving circuit from being arranged below the gaps **250** between the pixels, so as to effectively avoid adverse effects of the driving circuit on the overall light transmittance of the display screen **20**.

(82) It should be understood that in the embodiment of the present application, the configuration of the microlens layer **28** is a core factor affecting the light transmittance of the display screen **20**. Specifically, in the embodiment of the present application, the microlens layer **28** includes a series of microlens units **280**, preferably, the microlens units **280** are distributed in an array, and each microlens unit **280** corresponds to each gap **250** between the pixels **251**. Each microlens unit **280** has a light converging effect, that is, light radiated to each microlens unit **280** is refracted at each microlens unit **280** so as to be converged to the corresponding gap **250** between the pixels; and therefore, compared with that of the existing display screen **20**, the amount of light passing through each gap **250** is increased, that is, the overall light transmittance of the display screen **20** is increased.

(83) More specifically, in the embodiment of the present application, each microlens unit **280** is implemented as a convex lens having a light converging effect, wherein a convex face of the convex lens faces a front surface of the display screen **20**, a bottom surface of the convex lens faces each gap **250**, so that when light from the outside reaches the convex lens, the light from the outside is refracted at the convex face of the convex lens and converged to the gaps **250** between the pixels **251**, and thus, larger amount of light from the outside can pass through the pixel layer **25** via the gaps **250** between the pixels **251**. In a specific implementation, the convex lens can be implemented as a spherical convex lens, a non-spherical convex lens or a cylindrical lens (wherein a convex face of the cylindrical lens can be implemented as a spherical face or a non-spherical face), as shown in FIG. 4A and FIG. 4B, which is not limited in the present application.

(84) Preferably, the microlens layer **28** of the present invention is formed on the encapsulation layer

24, that is, the encapsulation layer **24** is used to encapsulate the pixel layer **25**, and itself has a light transmitting function. In the prior art, the encapsulation layer **24** is basically implemented as a glass cover plate or light transmitting encapsulation film. However, in the present invention, referring to FIG. 5, the encapsulation layer **24** is provided with a light transmitting area and a light converging area, wherein the light transmitting area is used to allow light emitted by the pixel layer **25** to be transmitted and displayed on the screen for imaging; and the light converging area is implemented as the microlens layer **28** for converging light. Further, in the process of preparing the encapsulation layer **24**, the microlens layer **28** is formed in a light transmitting area, for example, when the encapsulation layer **24** is formed by a process such as an injection molding process, a mold corresponding to the light transmitting area is designed to be in a shape of the microlens layer **28** so as to obtain the microlens layer **28** of the encapsulation layer **24**.

(85) More specifically, a preset position of the encapsulation layer **24** is set to protrude downward and upward, respectively, to form at least one microlens unit **280**. The encapsulation layer **24** has an upper surface and a lower surface, wherein at least part of the upper surface protrudes from the other part of the upper surface, at least part of the lower surface protrudes from the other part of the lower surface, the protruding part of the upper surface corresponds to the protruding part of the lower surface to form the light converging area, so as to form at least one microlens unit **280**, thereby integrally forming the microlens layer **28** on the encapsulation layer **24**.

(86) Further, in the embodiment of the present application, the microlens layer **28** can be integrally formed in each gap between the pixels **251** in the pixel layer **25**, so that each microlens unit **280** of the microlens layer **28** directly corresponds to each gap **250** between the pixels **251** to converge larger amount of light to each gap **250** between the pixels **251**, thereby increasing the light transmittance of the display screen **20**.

(87) For example, the microlens layer **28** of the present application can be prepared by, for example, a preparation process of forming a microlens layer **28** on a photosensitive chip. Certainly, the microlens layer **28** can also be formed on the pixel layer **25** by other process, which is not limited in the present application. Accordingly, bottom surfaces of various microlens units **280** of the formed microlens layer **28** are attached to the gaps **250** between various pixels **251** to cover the gaps **250**, and moreover, convex faces of various microlens units **280** protrude upward relative to the gaps **250** so as to converge light from the outside to the gaps **250**. Accordingly, the encapsulation layer **24** is integrally formed on the microlens layer **28** and the pixel layer **25** to encapsulate the pixel layer **25** and the microlens layer **28**. For example, the encapsulation layer **24** can be formed above the microlens layer **28** and the pixel layer **25** by a deposition process. The display screen described in the present embodiment can also be prepared by an etching process.

(88) Referring to FIG. 3B, a preparation method of the display screen **20** in FIG. 3A is shown. An encapsulation layer **24**, a pixel layer **25**, and a circuit driving layer **26** are first obtained, wherein the encapsulation layer **24** is supported on the pixel layer **25**, and the pixel layer **25** is supported on the circuit driving layer. The encapsulation layer **24** includes a first encapsulation layer part **241** and a second encapsulation layer part **242**, wherein the first encapsulation layer part **241** is made of a material with a relatively high refractive index, and the second encapsulation layer part **242** is made of a material with a relatively low refractive index. The first encapsulation layer part **241** of the encapsulation layer **24** corresponds to the gaps between adjacent pixels **251** of the pixel layer **25**, so that light can pass through the gaps between adjacent pixels **251** of the pixel layer **25** after passing through the first encapsulation layer part **241** of the encapsulation layer **24**.

(89) Further, the microlens layer **28** is integrally formed on the encapsulation layer **24**. Specifically, the first encapsulation layer part **241** of the encapsulation layer **24** is etched to form the microlens units **280**, the thickness of the microlens unit **280** can be equal to that of the second encapsulation layer part **242** of the encapsulation layer **24**, and the thickness of the microlens unit **280** can also be smaller than that of the first encapsulation layer part **241** of the encapsulation layer **24**.

(90) In the present example, the thickness of the microlens unit **280** is smaller than that of the first

encapsulation layer part **241** of the encapsulation layer **24**, a material same as that of the second encapsulation layer part **242** of the encapsulation layer **24** may be filled above the microlens units **280**, and the polarizing layer **23**, the touch layer **22** and the cover plate layer **21** are in sequence provided above the encapsulation layer **24**, and the back plate layer **27** with the opening hole is provided below the circuit driving layer **26** to obtain a complete display screen.

(91) Referring to FIG. 3C, another implementation mode based on the preparation method in FIG. 3B is shown. In the present embodiment, the thickness of the microlens layer **28** is smaller than that of the second encapsulation layer part **242** of the encapsulation layer **24**, and the polarizing layer **23** is directly provided above the encapsulation layer **24**, so that light passes through the polarizing layer **23**, a gap between the polarizing layer **23** and the microlens units **280**, the microlens layer **28**, and the gaps between adjacent pixels **251** of the pixel layer **25** in sequence to reach the circuit driving layer **26**.

(92) It is worthwhile to note that the microlens unit **280** formed by an etching process may further be coated or sprayed with an anti-reflection film or a material with a higher refractive index so as to increase the transmittance and refractive index of light at the position.

(93) Referring to FIG. 3D, another implementation mode based on the preparation method in FIG. 3B is shown. In the present embodiment, the thickness of the microlens layer **28** is smaller than that of the second encapsulation layer part **242** of the encapsulation layer **24**, and a light-transmissive material is filled between the microlens unit **280** and the encapsulation layer **24**, so that the microlens layer **28** is flush with the encapsulation layer **24**, and a refractive index of the filling material is different from that of a material of the second encapsulation layer part **242** of the encapsulation layer **24**. Then the polarizing layer **23** is provided above the encapsulation layer **24**, so that light passes through the polarizing layer **23**, a gap between the encapsulation layer **24** and the microlens units **280**, the microlens layer **28**, and the gaps between adjacent pixels **251** of the pixel layer **25** in sequence to reach the circuit driving layer **26**.

(94) It is worthwhile to note that the microlens unit **280** formed by an etching process may further be coated or sprayed with an anti-reflection film or a material with a higher refractive index so as to increase the transmittance and refractive index of light at the position.

(95) Referring to FIG. 3E, another implementation mode based on the preparation method in FIG. 3B is shown. In the present embodiment, the encapsulation layer **24** is first obtained, the encapsulation layer **24** includes two parts, wherein one part is a first encapsulation layer part **241**, and the other part is a second encapsulation layer part **242**, and the first encapsulation layer part **241** and the second encapsulation layer part **242** are spaced apart from each other. It is worthwhile to note that a size of a gap between the first encapsulation layer part **241** and the second encapsulation layer part **242** can be determined according to a size of the pixel **251** and a size of the gap between the pixels **251**. A refractive index of the first encapsulation layer part **241** is higher than that of the second encapsulation layer part **242**.

(96) The microlens units **280** are formed on the first encapsulation layer part **241** by an etching process so as to integrally form the microlens layer **28** on the encapsulation layer **24**. A thickness of the microlens unit **280** can be smaller than or equal to that of the encapsulation layer **24**.

(97) In the present example, the thickness of the microlens unit **280** is equal to that of the encapsulation layer **24**, and specifically, an upper light inlet face of the microlens unit **280** and an upper surface of the encapsulation layer **24** are on the same surface, and a lower light outlet face of the microlens unit **280** and a lower surface of the encapsulation layer **24** are on the same surface.

(98) In some embodiments of the present invention, the thickness of the microlens unit **280** is smaller than that of the encapsulation layer **24**, an upper light inlet face of the microlens unit **280** is lower than an upper surface of the encapsulation layer **24**, and a lower light outlet face of the microlens unit **280** and a lower surface of the encapsulation layer **24** are on the same surface. In another embodiment of the present invention, the upper light inlet face of the microlens layer **28** is lower than the upper surface of the encapsulation layer **24**, and the lower light outlet face of the

microlens layer **28** is higher than the lower surface of the encapsulation layer **24**.

(99) Then, a material is filled between the microlens unit **280** and the encapsulation layer **24**, and the filling material is same as a material of the second encapsulation layer part **242** of the encapsulation layer **24**.

(100) Then, the pixel layer **25** and the circuit driving layer **26** are mounted below the encapsulation layer **24**, and the microlens units **280** of the microlens layer **28** are aligned with the gaps between adjacent pixels **251** of the pixel layer **25**.

(101) Then, the polarizing layer **23**, the touch layer **22** and the cover plate layer **21** are mounted to obtain the display screen.

(102) Referring to FIG. 3F, another implementation mode of the preparation method of the display screen according to an embodiment of the present application is shown. The main difference is that the thickness of the microlens is smaller than that of the encapsulation layer **24**, and the upper light inlet face of the microlens is lower than the upper surface of the encapsulation layer **24**, and the lower light outlet face of the microlens is flush with the lower surface of the encapsulation layer **24**.

(103) The refractive index of the material filled between the encapsulation layer **24** and the microlens units **280** is higher than that of the material of the second encapsulation layer part **242** of the encapsulation layer **24**, and the material is filled above the microlens layer **28** and is flush with the encapsulation layer **24**.

(104) Then, the other layers are mounted on the encapsulation layer **24** to obtain the display screen.

(105) Referring to FIG. 3G, another implementation mode of the preparation method of the display screen according to an embodiment of the present application is shown. The main difference is that the thickness of the microlens is smaller than that of the encapsulation layer **24**, and the upper light inlet face of the microlens is lower than the upper surface of the encapsulation layer **24**, and the lower light outlet face of the microlens is higher than the lower surface of the encapsulation layer **24**.

(106) Then, the other layers are directly mounted on the encapsulation layer **24** to obtain the display screen.

(107) In the present example, light passes through a gap between the polarizing layer **23** and the microlens layer **28**, the microlens layer **28**, a gap between the microlens layer **28** and the pixel layer **25**, and the gaps between adjacent pixels **250** of the pixel layer **25** in sequence, and then finally reaches the circuit driving layer **26**.

(108) FIG. 6A is another variant implementation mode of the display screen **20** according to an embodiment of the present application. As shown in FIG. 6A, in the variant implementation mode, the microlens layer **28** is provided with a film structure which is pre-prepared and then attached to the pixel layer **25**, wherein with an attaching position of the microlens layer **28** and the arrangement of the microlens units **280** of the microlens layer **28**, when the microlens layer **28** is attached to the pixel layer **25**, each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** so as to increase the light transmittance of the display screen **20**. Accordingly, the encapsulation layer **24** is integrally formed on the microlens layer **28** and the pixel layer **25** to encapsulate the pixel layer **25** and the microlens layer **28**. For example, the encapsulation layer **24** can be formed above the microlens layer **28** and the pixel layer **25** by a deposition process. The preparation method in which the microlens layer is integrally formed on the pixel layer illustrated in FIG. 3B, FIG. 3C or FIG. 3D can also be applied to the present embodiment.

(109) It should be noted that in the specific examples of the display screen **20** illustrated in FIG. 4B and FIG. 6A, the microlens layer **28** is located inside the encapsulation layer **24**. In other words, a height size H of the microlens unit **280** (i.e. a height size of the microlens unit **280**) is smaller than or equal to that of the encapsulation layer **24**. When a height size of the microlens is equal to that of the encapsulation layer **24**, the microlens layer **28** is tangent to the top surface of the encapsulation layer **24**.

(110) Particularly, if the microlens unit **280** is implemented as a cylindrical lens, preferably, a width **W** of a bottom face of the cylindrical lens (i.e. a horizontal size of the microlens unit **280**) is larger than a size of the gap **250** between the pixels **251**, so that the cylindrical lens can completely cover the gap **250** between the pixels **251**. It should be understood that when the cylindrical lens completely covers the gap **250** between the pixels **251**, light originally falling outside the gap **250** can be diverted to the gap **250** between the pixels **251** by a light converging effect of the cylindrical lens, so that this part of light can pass through the pixel layer **25** via the gap **250**.

(111) Moreover, preferably, a length **L** of the bottom face of the cylindrical lens (i.e. a longitudinal size of the microlens unit **280**) is larger than or equal to the gap between adjacent pixels **251**, so that the cylindrical lens can completely cover the gap **250** between various pixels **251**, thereby increasing the amount of light converged to the gaps **250** between the pixels. More preferably, the length **L** of the bottom face of the cylindrical lens is an integer multiple of a size of a single gap between adjacent pixels **251**, for example, the length of the bottom face of the cylindrical lens can be set to be a size of a gap, and thus, an array formed by the cylindrical lenses can perfectly correspond to an array formed by the pixels **251**.

(112) To further enhance the light converging effect of the microlens layer **28**, preferably, in the embodiment of the present application, a refractive index of a material for forming the microlens layer **28** is higher than that of a material for forming the encapsulation layer **24**. It should be understood that the higher the refractive index is, the greater the light bending ability is, and therefore, when the microlens layer **28** has a higher refractive index, light originally falling outside the gaps **250** in a relatively larger range can be diverted to the gaps **250** between the pixels **251** through the light converging effect of the cylindrical lenses. It should be understood that the light converging effect increases as a difference between the refractive index of the microlens layer **28** and the refractive index of the encapsulation layer **24** increases.

(113) FIG. **6B** is another variant implementation mode of the display screen **20** according to an embodiment of the present application. As shown in FIG. **6B**, in the variant implementation mode, the microlens layer **28** is a film structure.

(114) Specifically, recessed structures are first etched at positions corresponding to the gaps between adjacent pixels **251** of the encapsulation layer **24**, and then coated with films, that is, the lower surface recessed inward of the encapsulation layer **24** is coated with a film to form a film structure, which can play the role of converging light.

(115) A certain gap may be reserved between the film structure and the pixel layer **25**. In the present example, a preset distance is reserved between the film structure and the pixel layer **25**. That is, the film structure is not in direct contact with the pixel layer **25**. After passing through the polarizing layer **23**, light passes through the encapsulation layer **24**, the film structure of the microlens layer **28**, the gap between the film structure and the pixel layer **25**, and the pixel layer **25** in sequence.

(116) FIG. **7** is yet another variant implementation mode of the display screen **20** according to an embodiment of the present application. As shown in FIG. **7**, in the variant implementation mode, the microlens layer **28** is provided with a film structure which is first pre-prepared and then attached to the encapsulation layer **24**, wherein with an attaching position of the microlens layer **28** and the arrangement of the microlens units **280** of the microlens layer **28**, when the microlens layer **28** is attached to the encapsulation layer **24**, each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** so as to increase the light transmittance of the display screen **20**.

(117) It is worthwhile to note that the polarizing layer **23** is provided with at least one accommodating space, wherein the accommodating space corresponds to the microlens units **280** of the microlens layer **28**, the accommodating space is set to match with the microlens units **280** with a film structure, and at least part of the microlens units **280** can be accommodated in the accommodating space of the polarizing layer **23**.

(118) A lower surface of the polarizing layer **23** and an upper surface of the microlens layer **28** are set to match with each other. In the present example, the lower surface of the polarizing layer **23** is set to at least partially recess inward, at least part of the upper surface of the microlens layer **28** is set to at least partially protrude outward, and the lower surface of the polarizing layer **23** can be attached to the upper surface of the microlens layer **28**.

(119) It should be seen that, compared with the display screens **20** in FIG. 5, FIG. 6A and FIG. 6B, in the variant embodiment, the microlens layer **28** is not in direct contact with the pixel layer **25**, that is, an encapsulation layer **24** is provided between the microlens layer **28** and the pixel layer **25**. However, each microlens unit **280** of the microlens layer **28** still corresponds to each gap **250** between the pixels **251**, and therefore, the microlens layer **28** can still converge a larger amount of light to each gap **250** between the pixels **251** so as to increase the light transmittance of the display screen **20**.

(120) FIG. 8A is yet another variant implementation mode of the display screen **20** according to an embodiment of the present application. As shown in FIG. 8A, in the variant implementation mode, the microlens layer **28** is integrally formed on the top surface of the encapsulation layer **24** in a recessed manner (for example, by an etching process). Specifically, at least part of the polarizing layer **23** is etched, so that a bottom surface of the polarizing layer **23** recesses inwardly, and then recessed positions of the bottom surface of the polarizing layer **23** are filled to form the microlens units **280**. The filling material can be a transparent material with a high refractive index.

(121) Further, by adjusting the amount of the filling material, the microlens units **280** can be flush with the polarizing layer **23**.

(122) With a position where the microlens layer **28** is formed and the arrangement of the microlens units **280** of the microlens layer **28**, when the microlens layer **28** is integrally formed on the top surface of the encapsulation layer **24**, each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** so as to increase the light transmittance of the display screen **20**.

(123) It is worthwhile to note that in the variant implementation mode, the microlens layer **28** and the encapsulation layer **24** are of an integral structure, which is advantageous for the preparation of the display screen **20**. For example, in the preparation process, the microlens layer **28** and the encapsulation layer **24** can be prepared as one element in a same process to reduce the preparation process and preparation cost of the display screen **20**.

(124) FIG. 8B is yet another variant implementation mode of the display screen **20** according to an embodiment of the present application. As shown in FIG. 8B, in the variant implementation mode, the microlens layer **28** is a film structure and is provided on the polarizing layer **23**.

(125) Specifically, recessed structures are first etched at positions corresponding to the gaps between adjacent pixels **251** of the polarizing layer **23**, and then coated with films, that is, the lower surface recessed inward of the polarizing layer **23** is coated with a film to form a film structure, which can play the role of converging light.

(126) A certain gap may be reserved between the film structure and the pixel layer **25**. In the present example, a preset distance is reserved between the film structure and the pixel layer **25**. That is, the film structure is not in direct contact with the pixel layer **25**. After passing through the polarizing layer **23**, light passes through the film structure of the microlens layer **28**, a gap between the film structure and the encapsulation layer **24**, and the encapsulation layer **24** in sequence to reach the pixel layer **25**.

(127) FIG. 9 is yet another variant implementation mode of the display screen **20** according to an embodiment of the present application. As shown in FIG. 9, in the variant implementation mode, the microlens layer **28** is integrally formed on the top surface of encapsulation layer **24** in a protruded manner (for example, by a deposition process), wherein with a position where the microlens layer **28** is formed and the arrangement of the microlens units **280** of the microlens layer **28**, when the microlens layer **28** is integrally formed on the top surface of the encapsulation layer

24, each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** so as to increase the light transmittance of the display screen **20**.

(128) It is worthwhile to note that in the variant implementation mode, the microlens layer **28** and the encapsulation layer **24** are of an integral structure, which is advantageous for the preparation of the display screen **20**. For example, in the preparation process, the microlens layer **28** and the encapsulation layer **24** can be prepared as one element in a same process to reduce the preparation process and preparation cost of the display screen **20**.

(129) In conclusion, the display screen **20** of the present application does not require a sharp adjustment to the existing structure of the existing display screen **20**, and only one microlens layer **28** corresponding to each gap **250** between the pixels in the pixel layer **25** needs to be additionally provided above the pixel layer **25** of the display screen **20**. Accordingly, the preparation process of the microlens layer **28** is relatively simple, the preparation efficiency is high, and cost is relatively low.

(130) Exemplary Preparation Method of a Display Screen

(131) According to another aspect of the present application, the present application further provides a preparation method of a display screen, which is used to prepare a display screen with relatively high transmittance.

(132) FIG. **10** is a schematic diagram of a preparation process of the display screen **20** according to an embodiment of the present application. As shown in FIG. **10**, in the preparation process, the circuit driving layer **26** is first pre-prepared, and the pixel layer **25** is formed on the circuit driving layer **26**, wherein the circuit driving layer **26** is electrically connected to the pixel layer **25** to drive the pixel layer **25** to operate. Those skilled in the art should know that at present, the mainstream production process of the pixel layer **25** in the OLED display screen is the evaporation process. In simple terms, the evaporation process is to use a method such as electric current heating, electron beam bombardment heating and laser heating in a vacuum to evaporate a material to be evaporated into atoms or molecules, which then move in a straight line with a larger free path, and collide with a surface of a substrate and condense to form a thin film. In addition, besides the evaporation process for “evaporating” each pixel **251** into the OLED screen, the printing process can also be used, that is, an organic material thin film of a display device is prepared in a printing manner.

(133) Further, as shown in FIG. **10**, the microlens layer **28** is integrally formed on the pixel layer **25**, wherein each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** in the pixel layer **25**. For example, the microlens units **280** can be respectively formed on the gaps **250** between various pixels **251** of the pixel layer **25** by a deposition process, and by this way, the microlens layer **28** is integrally formed on the pixel layer **25**.

(134) Further, as shown in FIG. **10**, the encapsulation layer **24** is formed on the microlens layer **28** and the pixel layer **25** to encapsulate the microlens layer **28** and the pixel layer **25** through the encapsulation layer **24**. For example, the encapsulation layer **24** can also be integrally formed on the pixel layer **25** and the microlens layer **28** by a deposition process to encapsulate the pixel layer **25** and the microlens layer **28** through the encapsulation layer **24**. Further, the polarizing layer **23**, the touch layer **22** and the cover plate layer **21** are formed in sequence on the encapsulation layer **24** to form the display screen **20** in a combined manner.

(135) Optionally, a back plate layer **27** provided with an opening hole **270** can further be attached to a bottom side of the circuit driving layer **26** to enhance the structural strength of the display screen **20** through the back plate layer **27**. Particularly, the opening hole **270** of the back plate layer **27** is formed at a light transmitting position of the display screen **20**.

(136) It should be understood that the microlens layer **28** is formed inside the encapsulation layer **24**, and corresponds to the gaps **250** between various pixels **251**, so that when light passes through the cover plate layer **21**, the touch layer **22**, the polarizing layer **23**, and the encapsulation layer **24** in sequence to reach the microlens layer **28**, the microlens layer **28** converges the light to the gaps

250 between various pixels 251, and thus, larger amount of light can pass through the pixel layer 25 via the gaps 250. Further, the light passing through the pixel layer 25 can pass through the circuit driving layer 26 to reach a bottom side of the display screen 20. Thus, the overall light transmittance of the display screen 20 can be effectively increased.

(137) Particularly, in the above preparation method, a refractive index of a material for forming the microlens layer 28 is higher than that of a material for forming the encapsulation layer 24.

(138) FIG. 11 is a schematic diagram of another preparation process of the display screen 20 according to an embodiment of the present application. As shown in FIG. 11, in the preparation process, the circuit driving layer 26 is first pre-prepared, and the pixel layer 25 is formed on the circuit driving layer 26, wherein the circuit driving layer 26 is electrically connected to the pixel layer 25 to drive the pixel layer 25 to operate. Those skilled in the art should know that at present, the mainstream production process of the pixel layer 25 in the OLED display screen is the evaporation process. In simple terms, the evaporation process is to use a method such as electric current heating, electron beam bombardment heating and laser heating in a vacuum to evaporate a material to be evaporated into atoms or molecules, which then move in a straight line with a larger free path, and collide with a surface of a substrate and condense to form a thin film. In addition, besides the evaporation process for “evaporating” each pixel 251 into the OLED screen, the printing process can also be used, that is, an organic material thin film of a display device is prepared in a printing manner.

(139) As shown in FIG. 11, further, the microlens layer 28 with a film structure is pre-prepared, and the microlens layer 28 is attached to the pixel layer 25. Particularly, in the embodiment of the present application, with an attaching position of the microlens layer 28 and the arrangement of the microlens units 280 of the microlens layer 28, when the microlens layer 28 is attached to the pixel layer 25, each microlens unit 280 of the microlens layer 28 corresponds to each gap 250 between the pixels 251 so as to increase the light transmittance of the display screen 20.

(140) As shown in FIG. 11, further, the encapsulation layer 24 is formed on the microlens layer 28 and the pixel layer 25 to encapsulate the microlens layer 28 and the pixel layer 25 through the encapsulation layer 24. For example, the encapsulation layer 24 can be integrally formed on the pixel layer 25 and the microlens layer 28 by a deposition process to encapsulate the pixel layer 25 and the microlens layer 28 through the encapsulation layer 24. Further, the polarizing layer 23, the touch layer 22 and the cover plate layer 21 are formed in sequence on the encapsulation layer 24 to form the display screen 20 in a combined manner.

(141) Optionally, a back plate layer 27 provided with an opening hole 270 can further be attached to a bottom side of the circuit driving layer 26 to enhance the structural strength of the display screen 20 through the back plate layer 27. Particularly, the opening hole 270 of the back plate layer 27 is formed at a light transmitting position of the display screen 20.

(142) It should be understood that the microlens layer 28 is located inside the encapsulation layer 24, and the microlens units 280 correspond to the gaps 250 between various pixels 251 in the pixel layer 25, so that when light passes through the cover plate layer 21, the touch layer 22, the polarizing layer 23, and the encapsulation layer 24 in sequence to reach the microlens layer 28, the microlens layer 28 converges the light to the gaps 250 between various pixels 251, and thus, larger amount of light can pass through the pixel layer 25 via the gaps 250. Further, the light passing through the pixel layer 25 can pass through the circuit driving layer 26 to reach a bottom side of the display screen 20. Thus, the overall light transmittance of the display screen 20 can be effectively increased.

(143) Particularly, in the above preparation method, a refractive index of a material for forming the microlens layer 28 is higher than that of a material for forming the encapsulation layer 24.

(144) FIG. 12 is a schematic diagram of yet another preparation process of the display screen 20 according to an embodiment of the present application. As shown in FIG. 12, in the preparation process, the circuit driving layer 26 is first pre-prepared, and the pixel layer 25 is formed on the

circuit driving layer **26**, wherein the circuit driving layer **26** is electrically connected to the pixel layer **25** to drive the pixel layer **25** to operate. Those skilled in the art should know that at present, the mainstream production process of the pixel layer **25** in the OLED display screen is the evaporation process. In simple terms, the evaporation process is to use a method such as electric current heating, electron beam bombardment heating and laser heating in a vacuum to evaporate a material to be evaporated into atoms or molecules, which then move in a straight line with a larger free path, and collide with a surface of a substrate and condense to form a thin film. In addition, besides the evaporation process for “evaporating” each pixel **251** into the OLED screen, the printing process can also be used, that is, an organic material thin film of a display device is prepared in a printing manner.

(145) As shown in FIG. **12**, further, an encapsulation layer **24** is integrally formed on the pixel layer **25** to encapsulate the pixel layer **25** through the encapsulation layer **24**. Further, a microlens layer **28** is integrally formed on a top surface of the encapsulation layer **24**, wherein the microlens layer **28** includes microlens units **280** distributed in an array, and each microlens unit **280** corresponds to each gap **250** between the pixels **251** of the pixel layer **25**.

(146) Specifically, in the preparation process, the microlens layer **28** is integrally formed on the top surface of the encapsulation layer **24** by a process such as a deposition process. As shown in FIG. **12**, the formed microlens layer **28** extends on the top surface of the encapsulation layer **24** in a protruded manner, and moreover, each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251**.

(147) It is worthwhile to note that the microlens layer **28** is integrally formed on the top surface of the encapsulation layer **24**, that is, the microlens layer **28** and the encapsulation layer **24** are of an integral structure, and therefore, in the preparation process, the microlens layer **28** can be integrally formed on the top surface of the encapsulation layer **24** in advance, and then the encapsulation layer **24** with the microlens layer **28** is attached above the pixel layer **25**, as shown in FIG. **13**.

(148) As shown in FIG. **12**, further, the polarizing layer **23**, the touch layer **22** and the cover plate layer **21** are formed in sequence on the microlens layer **28** to form the display screen **20** in a combined manner.

(149) Optionally, a back plate layer **27** provided with an opening hole **270** can further be attached to a bottom side of the circuit driving layer **26** to enhance the structural strength of the display screen **20** through the back plate layer **27**. Particularly, the opening hole **270** of the back plate layer **27** is formed at a light transmitting position of the display screen **20**.

(150) It should be understood that the microlens layer **28** is formed on a top side of the encapsulation layer **24**, and the microlens units **280** correspond to the gaps **250** between various pixels **251** in the pixel layer **25**, so that when light passes through the cover plate layer **21**, the touch layer **22**, and the polarizing layer **23** in sequence to reach the microlens layer **28**, the microlens layer **28** converges the light, then the light passes through the encapsulation layer **24** to reach the gaps **250** between various pixels **251**, and thus, larger amount of light can pass through the pixel layer **25** via the gaps **250**. Further, the light passing through the pixel layer **25** can pass through the circuit driving layer **26** to reach a bottom side of the display screen **20**. Thus, the overall light transmittance of the display screen **20** can be effectively increased.

(151) Particularly, in the above preparation method, a refractive index of a material for forming the microlens layer **28** is higher than that of a material for forming the encapsulation layer **24**.

(152) FIG. **14** is a schematic diagram of yet another preparation process of the display screen **20** according to an embodiment of the present application. As shown in FIG. **14**, in the preparation process, the circuit driving layer **26** is first pre-prepared, and the pixel layer **25** is formed on the circuit driving layer **26**, wherein the circuit driving layer **26** is electrically connected to the pixel layer **25** to drive the pixel layer **25** to operate. Those skilled in the art should know that at present, the mainstream production process of the pixel layer **25** in the OLED display screen is the evaporation process. In simple terms, the evaporation process is to use a method such as electric

current heating, electron beam bombardment heating and laser heating in a vacuum to evaporate a material to be evaporated into atoms or molecules, which then move in a straight line with a larger free path, and collide with a surface of a substrate and condense to form a thin film. In addition, besides the evaporation process for “evaporating” each pixel **251** into the OLED screen, the printing process can also be used, that is, an organic material thin film of a display device is prepared in a printing manner.

(153) As shown in FIG. **14**, further, an encapsulation layer **24** is integrally formed on the pixel layer **25** to encapsulate the pixel layer **25** through the encapsulation layer **24**. Further, a microlens layer **28** is integrally formed on a top surface of the encapsulation layer **24**, wherein the microlens layer **28** includes microlens units **280** distributed in an array, and each microlens unit **280** corresponds to each gap **250** between the pixels **251** of the pixel layer **25**.

(154) Specifically, in the preparation process, the microlens layer **28** is integrally formed on the top surface of the encapsulation layer **24** by a process such as an etching process. As shown in FIG. **14**, the formed microlens layer **28** is formed on the top surface of the encapsulation layer **24** in a recessed manner, and moreover, each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251**.

(155) It is worthwhile to note that the microlens layer **28** is integrally formed on the top surface of the encapsulation layer **24**, that is, the microlens layer **28** and the encapsulation layer **24** are of an integral structure, and therefore, in the preparation process, the microlens layer **28** can be integrally formed on the top surface of the encapsulation layer **24** in advance, and then the encapsulation layer **24** with the microlens layer **28** is attached above the pixel layer **25**, as shown in FIG. **15**.

(156) As shown in FIG. **14**, further, the polarizing layer **23**, the touch layer **22** and the cover plate layer **21** are formed in sequence on the microlens layer **28** to form the display screen **20** in a combined manner.

(157) Optionally, a back plate layer **27** provided with an opening hole **270** can further be attached to a bottom side of the circuit driving layer **26** to enhance the structural strength of the display screen **20** through the back plate layer **27**. Particularly, the opening hole **270** of the back plate layer **27** is formed at a light transmitting position of the display screen **20**.

(158) It should be understood that the microlens layer **28** is formed on a top side of the encapsulation layer **24**, and the microlens units **280** correspond to the gaps **250** between various pixels **251** in the pixel layer **25**, so that light passes through the cover plate layer **21**, the touch layer **22**, and the polarizing layer **23** in sequence to reach the microlens layer **28**, and when the light passes through the cover plate layer **21**, the touch layer **22**, the polarizing layer **23**, a gap between the polarizing layer **23** and the microlens layer **28**, and the microlens layer **28** in sequence, the microlens layer **28** converges the light, then the light passes through the encapsulation layer **24** to reach the gaps **250** between various pixels **251**, and thus, larger amount of light can pass through the pixel layer **25** via the gaps **250**. Further, the light passing through the pixel layer **25** can pass through the circuit driving layer **26** to reach a bottom side of the display screen **20**. Thus, the overall light transmittance of the display screen **20** can be effectively increased.

(159) Particularly, in the above preparation method, a refractive index of a material for forming the microlens layer **28** is higher than that of a material for forming the encapsulation layer **24**.

(160) FIG. **16** is a schematic diagram of yet another preparation process of the display screen **20** according to an embodiment of the present application. As shown in FIG. **16**, in the preparation process, the circuit driving layer **26** is first pre-prepared, and the pixel layer **25** is formed on the circuit driving layer **26**, wherein the circuit driving layer **26** is electrically connected to the pixel layer **25** to drive the pixel layer **25** to operate. Those skilled in the art should know that at present, the mainstream production process of the pixel layer **25** in the OLED display screen is the evaporation process. In simple terms, the evaporation process is to use a method such as electric current heating, electron beam bombardment heating and laser heating in a vacuum to evaporate a material to be evaporated into atoms or molecules, which then move in a straight line with a larger

free path, and collide with a surface of a substrate and condense to form a thin film. In addition, besides the evaporation process for “evaporating” each pixel **251** into the OLED screen, the printing process can also be used, that is, an organic material thin film of a display device is prepared in a printing manner.

(161) As shown in FIG. **16**, further, an encapsulation layer **24** is integrally formed on the pixel layer **25** to encapsulate the pixel layer **25** through the encapsulation layer **24**. Further, the microlens layer **28** with a film structure is pre-prepared, and the microlens layer **28** is attached to a top surface of the encapsulation layer **24**. Particularly, in the embodiment of the present application, with an attaching position of the microlens layer **28** and the arrangement of various microlens units **280** of the microlens layer **28**, when the microlens layer **28** is attached to the encapsulation layer **24**, each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** so as to increase the light transmittance of the display screen **20**.

(162) As shown in FIG. **16**, further, the polarizing layer **23**, the touch layer **22** and the cover plate layer **21** are formed in sequence on the microlens layer **28** to form the display screen **20** in a combined manner.

(163) Optionally, a back plate layer **27** provided with an opening hole **270** can further be attached to a bottom side of the circuit driving layer **26** to enhance the structural strength of the display screen **20** through the back plate layer **27**. Particularly, the opening hole **270** of the back plate layer **27** is formed at a light transmitting position of the display screen **20**.

(164) It should be understood that the microlens layer **28** is formed on a top side of the encapsulation layer **24**, and the microlens units **280** correspond to the gaps **250** between various pixels **251** in the pixel layer **25**, so that when light passes through the cover plate layer **21**, the touch layer **22**, and the polarizing layer **23** in sequence to reach the microlens layer **28**, the microlens layer **28** converges the light, then the light passes through the encapsulation layer **24** to reach the gaps **250** between various pixels **251**, and thus, larger amount of light can pass through the pixel layer **25** via the gaps **250**. Further, the light passing through the pixel layer **25** can pass through the circuit driving layer **26** to reach a bottom side of the display screen **20**. Thus, the overall light transmittance of the display screen **20** can be effectively increased.

(165) Particularly, in the above preparation method, a refractive index of a material for forming the microlens layer **28** is higher than that of a material for forming the encapsulation layer **24**.

(166) Exemplary terminal device According to yet another aspect of the present application, the present application further provides a terminal device which can be in various forms, for example, the terminal device described in the present application can include mobile terminals such as mobile phones, smart phones, laptops, PDAs (personal digital assistants), PADs (tablet personal computers), PMPs (portable multimedia players), navigation apparatuses, and smart watches, and fixed terminals such as digital TVs and desk computers. The present application will be described below by setting the terminal device to be a mobile terminal and assuming the mobile terminal to be a smart phone (as shown in FIG. **17**). However, it will be understood by those skilled in the art that the configuration according to the implementations of the present application can also be applied to a fixed type terminal in addition to elements specifically for mobile purposes. To facilitate understanding and description, the embodiments of the present application are all described by taking a smart phone as an example, and other application scenarios may refer to each other.

(167) FIG. **17** is a specific example of a terminal device according to an embodiment of the present application, wherein in the specific example, the terminal device is implemented as a smart phone. As shown in FIG. **17**, the terminal device includes a terminal main body **10**, a camera module **30**, and the above display screen **20**.

(168) The terminal main body **10** includes a housing **11** configured to form an outer shape of the terminal device, and a mainboard **12** used to mount components of a control circuit and a power supply circuit of the terminal device, wherein a size of the mainboard **12** is smaller than that of an

accommodating space defined by the housing **11**, so that the mainboard **12** can be “horizontally” mounted inside the housing **11**. The display screen **20** is mounted inside the housing **11**, and serves as a display module of the terminal device, wherein the display device **20** is electrically connected to the mainboard **12**, so that the display screen **20** is powered by the mainboard **12** to realize an image display function. Particularly, in the embodiment of the present application, the display screen **20** is mounted at a top opening of the housing **11** so as to define a top surface of the terminal device by the display screen **20**, and the camera module **30** is provided below the display screen **20** and accommodated in the housing **11**, and serves as a camera module of the terminal device.

(169) It should be understood that when the camera module **30** is provided below the display screen **20**, a screen-to-body ratio (a ratio of the display screen **20** to the top surface of the terminal device) of the terminal device can be further increased (can be increased to a limitation of 100%). In other words, in the embodiment of the present application, the camera module **30** is configured as an under-screen camera module **30**, which, together with the display screen **20**, is mounted at different height positions of the housing **11**, so that the camera module **30** is free from being an obstacle to increase the screen-to-body ratio.

(170) Preferably, in the embodiment of the present application, the housing **11** adopts a “narrow” frame design, that is, width sizes of edges of the housing **11** can be ignored relative to a width size of the display screen **20**. Thus, the screen-to-body ratio of the terminal device can be further increased (can be increased to a limitation of 100%).

(171) It should be noted that in the embodiment of the present application, the camera module **30** is provided below the display screen **20**. As previously described, an essential technical problem of the conventional terminal device which cannot implement the technical solution of the “under-screen camera module **30**” is that: when the camera module **30** is provided below the display screen **20**, it cannot collect sufficient amount of imaging light from the outside, which makes an imaging function of the camera module **30** difficult to achieve. Accordingly, in the embodiment of the present application, the light transmittance of the display screen **20** is effectively increased by additionally providing a microlens layer **28** in the display screen **20**, and a position where the camera module **30** is mounted below the display screen **20** corresponds to a position where the microlens layer **28** is located in the display screen **20**, and thus, when the camera module **30** is provided below the display screen **20**, imaging light from the outside can still pass through the display screen **20** (from its front face to its rear face) to reach the camera module **30** for imaging, as shown in FIG. **18**.

(172) Specifically, when the display screen **20** is implemented as the display screens **20** shown in FIG. **2** and FIG. **6**, an imaging path (or a photosensitive path) of the camera module **30** is that: first, light from the outside passes through the cover plate layer **21**, the touch layer **22**, the polarizing layer **23** and the encapsulation layer **24** of the display screen **20** to reach the microlens layer **28** provided on the pixel layer **25**, wherein each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** in the pixel layer **25**; then, the light reaching the microlens layer **28** is refracted at each microlens unit **280** and converged to the corresponding gap **250** between the pixels **251**, so that larger amount of light can pass through the pixel layer **25** via the gaps **250** between the pixels **251**; and then, the light passing through the pixel layer **25** can further pass through the circuit driving layer **26** and is collected by the camera module **30** provided below the circuit driving layer **26** to perform an imaging reaction.

(173) Specifically, when the display screen **20** is implemented as the display screens **20** shown in FIG. **7** to FIG. **9**, an imaging path (or a photosensitive path) of the camera module **30** is that: first, light from the outside passes through the cover plate layer **21**, the touch layer **22** and the polarizing layer **23** of the display screen **20** to reach the microlens layer **28** provided on the encapsulation layer **24**, wherein each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** in the pixel layer **25** and they are separated by the encapsulation layer **24**; then, the light reaching the microlens layer **28** is refracted at each microlens unit **280** and

converged to the corresponding gap **250** between the pixels **251**; then, the converged light passes through the encapsulation layer **24** and enters the corresponding gaps **250** between pixels **251**, by this way, larger amount of light can pass through the pixel layer **25** via the gaps **250** between the pixels **251**; and then, the light passing through the pixel layer **25** can further pass through the circuit driving layer **26** and is collected by the camera module **30** provided below the circuit driving layer **26** to perform an imaging reaction.

(174) It is worthwhile to note that when the display screen **20** is implemented as the display screen **20** shown in FIG. 3 (that is, the display screen **20** further includes a back plate layer **27** provided with an opening hole **270**), an imaging path (or a photosensitive path) of the camera module **30** is that: first, light from the outside passes through the cover plate layer **21**, the touch layer **22**, the polarizing layer **23** and the encapsulation layer **24** of the display screen **20** to reach the microlens layer **28** provided on the pixel layer **25**, wherein each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** in the pixel layer **25**; then, the light reaching the microlens layer **28** is refracted at each microlens unit **280** and converged to the corresponding gap **250** between the pixels **251**, so that larger amount of light can pass through the pixel layer **25** via the gaps **250** between the pixels **251**; and then, the light passing through the pixel layer **25** can further pass through the circuit driving layer **26** and the opening hole **270** of the back plate layer **27**, and is collected by the camera module **30** provided at a bottom of the display screen **20** to perform an imaging reaction.

(175) Or, an imaging path (or a photosensitive path) of the camera module **30** is that: first, light from the outside passes through the cover plate layer **21**, the touch layer **22** and the polarizing layer **23** of the display screen **20** to reach the microlens layer **28** provided on the encapsulation layer **24**, wherein each microlens unit **280** of the microlens layer **28** corresponds to each gap **250** between the pixels **251** in the pixel layer **25** and they are separated by the encapsulation layer **24**; then, the light reaching the microlens layer **28** is refracted at each microlens unit **280** and converged to the corresponding gap **250** between the pixels **251**; then, the converged light passes through the encapsulation layer **24** and enters the corresponding gaps **250** between pixels **251**, by this way, larger amount of light can pass through the pixel layer **25** via the gaps **250** between the pixels **251**; and then, the light passing through the pixel layer **25** can further pass through the circuit driving layer **26** and the opening hole **270** of the back plate layer **27**, and is collected by the camera module **30** provided at a bottom of the display screen **20** to perform an imaging reaction.

(176) Particularly, when the display screen **20** includes the back plate layer **27** provided at the bottom, optionally, the camera module **30** can be mounted below the display screen **20** and corresponds to the opening hole **270** of the back plate layer **27**; or, when a size of the opening hole **270** matches that of the camera module **30**, the camera module **30** can be directly mounted in the opening hole **270** of the back plate layer **27**, wherein by mounting the camera module **30** in the opening hole **270** of the back plate layer **27**, the light passing through the circuit driving layer **26** can be directly collected by the camera module **30**, and an overall height size of the terminal device can be reduced, which will be further described below.

(177) Although, due to the display screen **20** with relatively high light transmittance, the camera module **30** can be configured as an under-screen camera module **30**, thereby further increasing the screen-to-body ratio of the terminal device. However, in a spatial relationship, because the camera module **30** is provided below the display screen **20**, and both of them are accommodated in the housing **11** of the terminal device at the same time, a height size of the housing **11** needs to increase, that is, the overall height size of the terminal device needs to increase, which is inconsistent with the current trend of thin terminal devices.

(178) Accordingly, a technical solution of reducing the overall height size of the terminal device is previously provided. Specifically, when the display screen **20** is implemented as the display screen **20** shown in FIG. 3, that is, the display screen **20** includes a back plate layer **27** provided with an opening hole **270**, wherein the opening hole **270** corresponds to the microlens layer **28**.

Particularly, in order to reduce the overall height size of the terminal device, preferably, a size of the opening hole **270** of the back plate layer **27** matches that of the camera module **30**, so that the camera module **30** can be directly mounted in the opening hole **270** of the back plate layer **27**, as shown in FIG. **19**. In other words, in this case, the opening hole **270** of the back plate layer **27** is not only a light transmitting hole of the display screen **20**, but also a mounting reference hole of the camera module **30**. It should be understood that when the camera module **30** is mounted in the opening hole **270** of the back plate layer **27**, the overall height sizes of the display screen **20** and the camera module **30** can be effectively reduced, thereby reducing the overall height size of the terminal device.

(179) It should be understood that when the size of the opening hole **270** of the back plate layer **27** does not match that of the camera module **30**, for example, when the size of the opening hole **270** is larger than that of the camera module **30**, the terminal device can be further provided with an auxiliary mounting piece **13**, wherein the auxiliary mounting piece **13** is mounted in the opening hole **270** of the back plate, and is used to mount the camera module **30** therein, as shown in FIG. **20**. For example, the auxiliary mounting piece **13** can be implemented as a tubular piece with a through hole, wherein an outer diameter of the tubular piece is equal to an aperture diameter of the opening hole **270**, an inner diameter of the through hole of the tubular piece matches the size of the camera module **30**, so that the camera module **30** can still be mounted in the opening hole **270** of the back plate layer **27** by using the tubular piece. Preferably, a height of the tubular piece is equal to or slightly smaller than that of the opening hole **270**, and thus, when the camera module **30** is mounted in the through hole of the tubular piece, the overall height sizes of the camera module **30** and the display screen **20** can be reduced, thereby directly mounting the camera module **30** in the opening hole **270** of the back plate layer **27**.

(180) To further reduce the overall height size of the terminal device, preferably, in the embodiment of the present application, a camera module **30** with a relatively low height size is adopted.

(181) FIG. **21** is a specific example of the camera module **30** according to an embodiment of the present application. As shown in FIG. **21**, in the specific example, the camera module **30** includes a circuit board **31**, a photosensitive chip **32**, and a light transmitting component **33**, wherein the circuit board **31** has a groove **310**, the photosensitive chip **32** is provided in the groove **310** and electrically connected to the circuit board **31**, and the light transmitting component **33** is located on a photosensitive path of the photosensitive chip **32**. Thus, imaging light passing through the display screen **20** first reaches the light transmitting component **33** and then the photosensitive chip **32**, and is sensed by the photosensitive chip **32** to perform an imaging reaction.

(182) Those skilled in the art should know that in an existing COB process-based camera module, a circuit board has a flat surface, and moreover, a photosensitive chip is directly attached to and is electrically connected to the flat surface of the circuit board. Each camera module has a preset optical back focus requirement, and therefore, a mounting reference height of the photosensitive chip directly determines the overall height size of the camera module **30**.

(183) Accordingly, compared with the existing COB process-based camera module, in the specific example, the circuit board **31** is provided with the groove **310** to reduce the mounting reference height of the photosensitive chip **32** through the groove **310**. In other words, in the embodiment of the present application, a top surface of the circuit board **31** is a non-flat surface, wherein an area for mounting the photosensitive chip **32** of the circuit board **31** recesses downward to reduce the mounting reference height of the photosensitive chip **32**. It should be understood that under the premise that the optical back focus requirement remains unchanged, a mounting height of an optical lens **332** relative to the circuit board **31** can be reduced, and thus the overall height size of the camera module **30** can be reduced.

(184) Preferably, in the specific example, a size of the groove **310** is consistent with that of the photosensitive chip **32**, and thus the groove **310** itself can be used to position and limit the photosensitive chip **32**. Specifically, in the process of mounting the photosensitive chip **32** in the

groove **310**, the photosensitive chip **32** can be directly embedded into the groove **310** snugly, and it is unnecessary to continuously calibrate and position a mounting position of the photosensitive chip on the circuit board as in the existing COB process-based camera module. Further, after the photosensitive chip **32** is mounted in the groove **310** and electrically connected to the circuit board **31**, the photosensitive chip **32** is “limited” in the groove **310** to prevent the photosensitive chip **32** from being separated or shifted from the groove **310**.

(185) Further, the camera module **30** further includes a group of leads **34**, wherein after the photosensitive chip **32** is attached in the groove **310** of the circuit board **31**, electrical connection between the photosensitive chip **32** and the circuit board **31** is realized through the leads **34**. Specifically, each lead **34** is bent and extended between the photosensitive chip **32** and the circuit board **31** to connect the photosensitive chip **32** to the circuit board **31** through the lead **34**. Thus, the circuit board **31** can supply power to the photosensitive chip **32** via the leads **34**, and the photosensitive chip **32** can transmit collected signals via the leads **34**.

(186) It is worthwhile to note that in the specific example, the type of the lead **34** is not limited in the present application, for example, the lead **34** may be a gold wire, a silver wire or a copper wire. Moreover, the leads **34** can be mounted between the circuit board **31** and the photosensitive chip **32** by a “wire bonding” process to realize the electrical connection therebetween.

(187) Specifically, the “wire bonding” process is generally divided into two types: a “forward wire bonding” process and a “reverse wire bonding” process. The “forward wire bonding” process refers to that in the process of laying the leads **34**, one end of the lead **34** is first formed at a conductive end of the circuit board **31**, then the lead **34** is bent and extended, and finally the other end of the lead **34** is formed at a conductive end of the photosensitive chip **32**. By this way, the leads **34** are formed between the photosensitive chip **32** and the circuit board **31**. The “reverse wire bonding” process refers to that in the process of laying the leads **34**, one end of the lead **34** is formed at the conductive end of the photosensitive chip **32**, then the lead **34** is bent and extended, and finally the other end of the lead **34** is formed at the conductive end of the circuit board **31**. By this way, the leads **34** are formed between the photosensitive chip **32** and the circuit board **31**. It is worthwhile to note that a height of an upward protrusion of the lead **34** formed by the “reverse wire bonding” process is lower than that of an upward protrusion of the lead **34** formed by the “forward wire bonding” process. Therefore, preferably, in the specific implementation, the leads **34** are formed by the “reverse wire bonding” process.

(188) Further, the camera module **30** further includes a base **35**, wherein the base **35** is provided on the circuit board **31** to support the light transmitting component **33**. The light transmitting component **33** includes a color filtering element **331** and an optical lens **332**, wherein the color filtering element **331** and the optical lens **332** are in sequence provided on the photosensitive path of the photosensitive chip **32**.

(189) Specifically, in the specific example, the base **35** can be implemented as a conventional plastic support, which is pre-prepared and then attached to a top surface of the circuit board **31**; or, the base **35** can be implemented as a molded base, which can be integrally formed at a corresponding position of the circuit board **31** and/or the photosensitive chip **32** by an MOB (Molding on Board) or MOC (molding on Chip) process. Those skilled in the art should know that the MOB (Molding on Board) process refers to that the molded base is integrally formed on the circuit board **31** by a molding process, wherein the formed molded base integrally covers the circuit board **31** and electrical elements **312** on the circuit board **31**. The MOC process refers to that the molded base is integrally formed on the circuit board **31** by a molding process, wherein besides the circuit board **31** and the electrical elements **312** on the circuit board **31**, the formed molded base further covers at least part of the leads **34**, or, covers the leads **34** and at least part of the photosensitive chip **32** (wherein the at least part of the photosensitive chip **32** is a non-photosensitive area of the photosensitive chip **32**).

(190) In the specific example, the color filtering element **331** is provided between the optical lens

332 and a photosensitive element, so that light entering the camera module **30** via the optical lens **332** is filtered by the color filtering element **331**, and then is received and photo-electrically converted by the photosensitive chip **32**, thereby improving the imaging quality of the camera module **30**. For example, the color filtering element **331** can be used to filter infrared rays in the light entering the camera module **30** via the optical lens **332**.

(191) Those skilled in the art should know that the color filtering element **331** can be implemented into different types, which include but are not limited to, an infrared ray cut-off filter, a full-transmittance spectral filter, other filters, and a combination of multiple filters. Specifically, for example, when the color filtering element **331** is implemented as a combination of an infrared ray cut-off filter and a full-transmittance spectral filter, that is, the infrared ray cut-off filter and the full-transmittance spectral filter can be switched to be selectively located on the photosensitive path of the photosensitive chip **32**, and by this way, when the camera module **30** is used in an environment with sufficient amount of light such as daytime, the infrared ray cut-off filter can be switched to the photosensitive path of the photosensitive chip **32** to filter infrared rays in light which is reflected by an object and enters the camera module **30** through the infrared ray cut-off filter. Moreover, when the camera module **30** is used in an environment with dark light such as night, the full-transmittance spectral filter can be switched to the photosensitive path of the photosensitive chip **32** to allow infrared rays in light which is reflected by an object and enters the camera module **30** to be transmitted.

(192) It is worthwhile to note that the color filtering element **331** can also be provided at another position on the photosensitive path of the photosensitive chip **32**, for example, the color filtering element **331** is provided at a bottom side of the optical lens **332**, or a bottom part of the optical lens **332**, which is not limited in the present application.

(193) In addition, it is worthwhile to note that in the specific example, the camera module **30** can be implemented as a fixed focus module or a dynamic focus module, wherein when the camera module **30** is a dynamic focus module, the camera module **30** further includes a driver **36** connected to the circuit board **31**, and the driver **36** is used to controllably drive the lens to move so as to realize auto-focus (Auto-Focus).

(194) FIG. **22** is another specific example of the camera module **30** according to an embodiment of the present application, wherein the camera module **30** in FIG. **22** is a variant implementation mode of the camera module **30** in FIG. **21**.

(195) Specifically, as shown in FIG. **22**, in the specific example, the camera module **30** includes a circuit board **31**, a photosensitive chip **32**, a light transmitting component **33**, and a reinforcement plate **37**, wherein the circuit board **31** has an opening hole **310A** penetrating through the circuit board **31**, the reinforcement plate **37** is attached to a bottom surface of the circuit board **31**, the photosensitive chip **32** is provided in the opening hole **310A** of the circuit board **31** and is attached to the reinforcement plate **37**, the photosensitive chip **32** can be conductively connected to the circuit board **31**, and the light transmitting component **33** is provided on a photosensitive path of the photosensitive chip **32**. Thus, imaging light passing through the display screen **20** first reaches the light transmitting component **33** and then the photosensitive chip **32**, and is sensed by the photosensitive chip **32** to perform an imaging reaction.

(196) In other words, compared with the camera module **30** in FIG. **21**, in the specific example, the circuit board **31** has the opening hole **310A** penetrating through the circuit board **31**, so that a mounting reference height of the photosensitive chip **32** is reduced through the opening hole **310A**. In other words, in the embodiment of the present application, a top surface of the circuit board **31** is a non-flat surface, wherein an area for mounting the photosensitive chip **32** of the circuit board **31** recesses downward and penetrates through the circuit **31**, so that the mounting reference height of the photosensitive chip **32** can be further reduced. It should be understood that each camera module has a preset optical back focus requirement, so that under the premise that the optical back focus requirement remains unchanged, a mounting height of the optical lens **332** relative to the circuit

board **31** can be further reduced, thereby further reducing the overall height size of the camera module **30**.

(197) As shown in FIG. **22**, it should be specially noted that in the specific example, a bottom surface of the photosensitive chip **32** is flush with a bottom surface of the circuit board **31**, that is, the mounting reference height of the photosensitive chip **32** is equal to a height of the bottom surface of the circuit board **31**, so that under the premise of ensuring the preset optical back focus, a mounting position of the photosensitive chip **32** can be further lowered, thereby further reducing the overall height size of the camera module **30**.

(198) Preferably, in the specific example, a size of the opening hole **310A** is consistent with that of the photosensitive chip **32**, and thus the opening hole **310** itself can be used to position and limit the photosensitive chip **32**. Specifically, in the process of mounting the photosensitive chip **32** in the opening hole **310A**, the photosensitive chip **32** can be directly embedded into the opening hole **310** snugly and finally attached to the reinforcement plate **37**, and it is unnecessary to continuously calibrate and position the mounting position of the photosensitive chip **32** on the circuit board **31** as in the existing COB process-based camera module. Further, after the photosensitive chip **32** is mounted in the opening hole **310A** and electrically connected to the circuit board **31**, the photosensitive chip **32** is “limited” in the opening hole **310A** to prevent the photosensitive chip **32** from being separated or shifted from the opening hole **310**.

(199) Further, the camera module **30** further includes a group of leads **34**, wherein after the photosensitive chip **32** is mounted in the opening hole **310A** of the circuit board **31**, electrical connection between the photosensitive chip **32** and the circuit board **31** is realized through the leads **34**. Specifically, each lead **34** is bent and extended between the photosensitive chip **32** and the circuit board **31** to connect the photosensitive chip **32** to the circuit board **31** through the lead **34**. Thus, the circuit board **31** can supply power to the photosensitive chip **32** through the leads **34**, and the photosensitive chip **32** can transmit collected signals through the leads **34**.

(200) It is worthwhile to note that in the specific example, the type of the lead **34** is not limited in the present application, for example, the lead **34** may be a gold wire, a silver wire or a copper wire. Moreover, the leads **34** can be mounted between the circuit board **31** and the photosensitive chip **32** by a “wire bonding” process to realize the electrical connection therebetween.

(201) Specifically, the “wire bonding” process is generally divided into two types: a “forward wire bonding” process and a “reverse wire bonding” process. The “forward wire bonding” process refers to that in the process of laying the leads **34**, one end of the lead **34** is first formed at a conductive end of the circuit board **31**, then the lead **34** is bent and extended, and finally the other end of the lead **34** is formed at a conductive end of the photosensitive chip **32**. By this way, the leads **34** are formed between the photosensitive chip **32** and the circuit board **31**. The “reverse wire bonding” process refers to that in the process of laying the leads **34**, one end of the lead **34** is formed at the conductive end of the photosensitive chip **32**, then the lead **34** is bent and extended, and finally the other end of the lead **34** is formed at the conductive end of the circuit board **31**. By this way, the leads **34** are formed between the photosensitive chip **32** and the circuit board **31**. It is worthwhile to note that a height of an upward protrusion of the lead **34** formed by the “reverse wire bonding” process is lower than that of an upward protrusion of the lead **34** formed by the “forward wire bonding” process. Therefore, preferably, in the specific implementation, the leads **34** are formed by the “reverse wire bonding” process.

(202) Further, the camera module **30** further includes a base **35**, wherein the base **35** is provided on the circuit board **31** to support the light transmitting component **33**. The light transmitting component **33** includes a color filtering element **331** and an optical lens **332**, wherein the color filtering element **331** and the optical lens **332** are in sequence provided on the photosensitive path of the photosensitive chip **32**.

(203) Specifically, in the specific example, the base **35** can be implemented as a conventional plastic support, which is pre-prepared and then attached to a top surface of the circuit board **31**; or,

the base **35** can be implemented as a molded base, which can be integrally formed at a corresponding position of the circuit board **31** and/or the photosensitive chip **32** by an MOB (Molding on Board) or MOC (molding on Chip) process. Those skilled in the art should know that the MOB (Molding on Board) process refers to that the molded base is integrally formed on the circuit board **31** by a molding process, wherein the formed molded base integrally covers the circuit board **31** and electrical elements **312** on the circuit board **31**. The MOC process refers to that the molded base is integrally formed on the circuit board **31** by a molding process, wherein besides the circuit board **31** and the electrical elements **312** on the circuit board **31**, the formed molded base further covers at least part of the leads **34**, or, covers the leads **34** and at least part of the photosensitive chip **32** (wherein the at least part of the photosensitive chip **32** is a non-photosensitive area of the photosensitive chip **32**).

(204) In the specific example, the color filtering element **331** is provided between the optical lens **332** and the photosensitive element, so that light entering the camera module **30** via the optical lens **332** is filtered by the color filtering element **331**, and then is received and photo-electrically converted by the photosensitive chip **32**, thereby improving the imaging quality of the camera module **30**. For example, the color filtering element **331** can be used to filter infrared rays in the light entering the camera module **30** via the optical lens **332**.

(205) Those skilled in the art should know that the color filtering element **331** can be implemented into different types, which include but are not limited to, an infrared ray cut-off filter, a full-transmittance spectral filter, other filters, and a combination of multiple filters. Specifically, for example, when the color filtering element **331** is implemented as a combination of an infrared ray cut-off filter and a full-transmittance spectral filter, that is, the infrared ray cut-off filter and the full-transmittance spectral filter can be switched to be selectively located on the photosensitive path of the photosensitive chip **32**, and by this way, when the camera module **30** is used in an environment with sufficient amount of light such as daytime, the infrared ray cut-off filter can be switched to the photosensitive path of the photosensitive chip **32** to filter infrared rays in light which is reflected by an object and enters the camera module **30** through the infrared ray cut-off filter. Moreover, when the camera module **30** is used in an environment with dark light such as night, the full-transmittance spectral filter can be switched to the photosensitive path of the photosensitive chip **32** to allow infrared rays in light which is reflected by an object and enters the camera module **30** to be transmitted.

(206) It is worthwhile to note that the color filtering element **331** can also be provided at another position on the photosensitive path of the photosensitive chip **32**, for example, the color filtering element **331** is provided at a bottom side of the optical lens **332**, or a bottom part of the optical lens **332**, which is not limited in the present application.

(207) It is also worthwhile to note that in the specific example, the camera module **30** can be implemented as a fixed focus module or a dynamic focus module, wherein when the camera module **30** is a dynamic focus module, the camera module **30** further includes a driver **36** electrically connected to the circuit board **31**, and the driver **36** is used to controllably drive the lens to move so as to realize auto-focus (Auto-Focus).

(208) FIG. **23** is yet another specific example of the camera module **30** according to an embodiment of the present application, wherein the camera module **30** in FIG. **23** is a variant implementation mode of the camera module **30** in FIG. **22**.

(209) Specifically, compared with the camera module **30** in FIG. **22**, in the specific example, the base **35** is directly provided on the reinforcement plate **37**. In other words, in the specific example, a mounting reference height of the base **35** can be reduced, so that a mounting reference height of the optical lens **332** mounted on the base **35** can be reduced, thereby reducing the overall height size of the camera module **30**.

(210) Accordingly, in the specific embodiment, the base **35** can be implemented as a conventional plastic support, which is pre-prepared and then attached to a top surface of the reinforcement plate

37; or, the based **35** can be implemented as a molded base, which can be integrally formed at a corresponding position of the reinforcement plate **37**, the circuit board **31** and/or the photosensitive chip **32** by an MOB (Molding on Board) or MOC (Molding on Chip) process. Those skilled in the art should know that the MOB (Molding on Board) process refers to that the molded base is integrally formed on the circuit board **31** by a molding process, wherein the formed molded base integrally covers the reinforcement plate **37**, the circuit board **31**, and electrical elements **312** on the circuit board **31**. The MOC process refers to that the molded base is integrally formed on the circuit board **31** by a molding process, wherein besides the reinforcement plate **37**, the circuit board **31** and the electrical elements **312** on the circuit board **31**, the formed molded base further covers at least part of the leads **34**, or, covers the leads **34** and at least part of the photosensitive chip **32** (wherein the at least part of the photosensitive chip **32** is a non-photosensitive area of the photosensitive chip **32**).

(211) FIG. **24** is yet another specific example of the camera module **30** according to an embodiment of the present application, wherein the camera module **30** in FIG. **24** is another variant implementation mode of the camera module **30** in FIG. **22**.

(212) Specifically, compared with the camera module **30** in FIG. **22**, in the specific example, the base **35** is provided with at least two positioning pillars **351** extending downward, the circuit board **31** is provided with at least two openings **311**, and the positioning pillars **351** pass through the openings **311** and are set on the reinforcement plate **37**. By this way, a mounting reference height of the base **35** can be reduced, thereby reducing the overall height size of the camera module **30**. FIG. **25** and FIG. **26** are yet another specific examples of the camera module **30** according to embodiments of the present application, wherein the camera modules **30** in FIG. **25** and FIG. **26** are yet another variant implementation modes of the camera module **30** in FIG. **22**.

(213) As shown in FIG. **25** and FIG. **26**, in the specific examples, a boss **371A** or a groove **371** is provided at a position, corresponding to the opening hole **310A** of the circuit board **31**, of the reinforcement plate **37**, so that a mounting reference height of the photosensitive chip **32** is adjusted through the boss **371A** or the groove **371**. In other words, in the specific examples, a bottom surface of the photosensitive chip **32** is not flush with that of the circuit board **31**.

(214) Specifically, as shown in FIG. **25**, when the groove **371** is provided at the position, corresponding to the opening hole **310A** of the circuit board **31**, of the reinforcement plate **37**, the mounting reference height of the photosensitive chip **32** is further reduced, so that under the premise of meeting the design requirement of the preset optical back focus, the overall height size of the camera module **30** can be further reduced. It should be noted that when the groove **371** is provided at the position, corresponding to the opening hole **310A** of the circuit **31**, of the reinforcement plate **37**, the photosensitive chip **32** is attached to the reinforcement plate **37**, and at this moment, the bottom surface of the photosensitive chip **32** is lower than that of the circuit board **31**.

(215) Specifically, as shown in FIG. **26**, when the boss **371A** is provided at the position, corresponding to the opening hole **310A** of the circuit board **31**, of the reinforcement plate **37**, compared with the existing COB process-based camera module, the mounting reference height of the photosensitive chip **32** is reduced, so that under the premise of meeting the design requirement of the preset optical back focus, the overall height size of the camera module **30** can be reduced. It should be noted that when the boss **371A** is provided at the position, corresponding to the opening hole **310A** of the circuit board **31**, of the reinforcement plate **37**, the photosensitive chip **32** is attached to the reinforcement plate **37**, and at this moment, the bottom surface of the photosensitive chip **32** is higher than that of the circuit board **31** but is lower than a top surface of the circuit board **31**.

(216) FIG. **27** is yet another specific example of the camera module **30** according to an embodiment of the present application, wherein the camera module **30** in FIG. **27** is a variant implementation mode of the camera module **30** in FIG. **24**.

(217) Specifically, as shown in FIG. 27, in the specific example, the camera module 30 includes a circuit board 31, a photosensitive chip 32, a base 35, an optical lens 332, a color filtering element 331, and a reinforcement plate 37, wherein the circuit board 31 is provided with an opening hole 310A penetrating through the circuit board 31, the reinforcement plate 37 is attached to a bottom surface of the circuit board 31, the photosensitive chip 32 is provided in the opening hole 310A of the circuit board 31 and attached to the reinforcement plate 37, the photosensitive chip 32 can be conductively connected to the circuit board 31, the color filtering element 331 and the optical lens 332 are in sequence provided on a photosensitive path of the photosensitive chip 32. Thus, imaging light passing through the display screen 20 first reaches the optical lens 332, then is filtered by the color filtering element 331, and reaches the photosensitive chip 32 to be sensed by the photosensitive chip 32 to perform an imaging reaction.

(218) Particularly, in the specific embodiment, the optical lens 332 and the base 35 are of an integral structure, that is, the optical lens 332 and the base 35 are assembled into a whole before being assembled into the camera module 30. In other words, in the specific example, the optical lens 332 is an integrated lens 333, which is assembled with the base 35 to form one element unit. Further, in the specific example, the base 35 is provided with at least two positioning pillars extending downward, and the circuit board 31 is provided with at least two openings, and the positioning pillars penetrate through the openings and are set on the reinforcement plate 37. By this way, the integrated lens 333 and the photosensitive chip 32 have the same mounting reference face (i.e. a top surface of the reinforcement plate 37). Thus, under the premise of meeting the design requirement of the preset optical back focus, the overall height size of the camera module 30 can be reduced.

(219) It is worthwhile to note that in the specific example of the present application, the integrated lens 333 can further include the color filtering unit 331, that is, in the specific implementation, the optical lens 332, the base 35 and the color filtering unit 331 are of an integral structure, that is, the optical lens 332, the base 35 and the color filtering unit 331 are assembled into a whole before being assembled into the camera module 30. Thus, an assembly method of the camera module 30 can be more compact, so that the overall height size of the camera module 30 can be reduced.

(220) FIG. 28 is yet another specific example of the camera module 30 according to an embodiment of the present application. As shown in FIG. 28, in the specific example, the camera module 30 includes an optical lens 332, a base 35, a color filtering element 331, a photosensitive chip 32, and a circuit board 31, wherein the photosensitive chip 32 can be conductively provided on the circuit board 31, the base 35 is provided on the circuit board 31, the lens and the color filtering element 331 are in sequence provided on a photosensitive path of the photosensitive chip 32, and the base 35 is used to support the color filtering element 331. Thus, imaging light passing through the display screen 20 first reaches the optical lens 332, then is filtered by the color filtering element 331, and reaches the photosensitive chip 32 to be sensed by the photosensitive chip 32 to perform an imaging reaction.

(221) Further, the camera module 30 further includes a group of leads 34, wherein after the photosensitive chip 32 is attached to the circuit board, electrical connection between the photosensitive chip 32 and the circuit board 31 is realized through the leads 34. Specifically, each lead 34 is bent and extended between the photosensitive chip 32 and the circuit board 31 to connect the photosensitive chip 32 to the circuit board 31 through the lead 34. Thus, the circuit board 31 can supply power to the photosensitive chip 32 via the leads 34, and the photosensitive chip 32 can transmit collected signals via the leads 34.

(222) It is worthwhile to note that in the specific example, the type of the lead 34 is not limited in the present application, for example, the lead 34 may be a gold wire, a silver wire or a copper wire. Moreover, the leads 34 can be mounted between the circuit board 31 and the photosensitive chip 32 by a “wire bonding” process to realize the electrical connection therebetween.

(223) Specifically, the “wire bonding” process is generally divided into two types: a “forward wire

bonding” process and a “reverse wire bonding” process. The “forward wire bonding” process refers to that in the process of laying the leads **34**, one end of the lead **34** is first formed at a conductive end of the circuit board **31**, then the lead **34** is bent and extended, and finally the other end of the lead **34** is formed at a conductive end of the photosensitive chip **32**. By this way, the leads **34** are formed between the photosensitive chip **32** and the circuit board **31**. The “reverse wire bonding” process refers to that in the process of laying the leads **34**, one end of the lead **34** is formed at the conductive end of the photosensitive chip **32**, then the lead **34** is bent and extended, and finally the other end of the lead **34** is formed at the conductive end of the circuit board **31**. By this way, the leads **34** are formed between the photosensitive chip **32** and the circuit board **31**. It is worthwhile to note that a height of an upward protrusion of the lead **34** formed by the “reverse wire bonding” process is lower than that of an upward protrusion of the lead **34** formed by the “forward wire bonding” process. Therefore, preferably, in the specific implementation, the leads **34** are formed by the “reverse wire bonding” process.

(224) The circuit board **31** is further provided with a group of electrical elements **312**, wherein the electrical elements **312** can be attached to a marginal area (relative to a position for attaching the photosensitive chip **32**) of the circuit board **31** at intervals by an SMT (Surface Mount Technology) process. The electrical elements **312** include but are not limited to resistors, capacitors, inductor, etc. It is worthwhile to note that the photosensitive chip **32** and each electrical element **312** can be located at the same side or different sides of the circuit board **31** respectively. For example, the photosensitive chip **32** and each electrical element **312** can be located at the same side of the circuit board **31** respectively, and the electrical elements **312** are attached to the marginal area of the circuit board **31** at intervals.

(225) Particularly, as shown in FIG. **28**, in the specific example, the base **35** is supported on a top surface of the circuit board **31**. Moreover, the base **35** includes a main body **352** and side walls **353** extending downward along the main body **352**, wherein an accommodating cavity **354** is defined by the main body **352** and the side walls **353**. When the base **35** is provided on the circuit board **31**, the side walls **353** are supported on the circuit board **31**, and the accommodating cavity **354** is defined by a bottom surface of the base **35**, an upper surface of the circuit board **31** and the side walls **353** together, wherein the electrical elements **312** provided on the circuit board **31** are accommodated in the accommodating cavity **354**. Preferably, a height size of the accommodating cavity **354** is less than 0.2 mm, such as 0.1 mm.

(226) Further, as shown in FIG. **28**, in the specific example, the base **35** is further provided with at least one accommodating hole **355**, wherein the accommodating hole **355** penetrates through the base **35** to communicate the accommodating cavity **354** with the external environment. It is worthwhile to note that in the specific embodiment, the height size of the accommodating cavity **354** is smaller than that of a relatively high electrical element **312**, for example, a capacitor. Therefore, when the base **35** is provided on the circuit board **31**, because a height from a bottom surface of the main body **352** of the base **35** to a top surface of the circuit board **31** is lower than that of the relatively high electrical element **312** such as a capacitor, if the accommodating hole **355** is not provided, the above electrical element **312** can be accommodated. That is, the accommodating hole **355** is used to avoid the high electrical element **312**, so that in the case where a height of the base **35** is reduced, the electrical element **312** can still be accommodated in the base **35**. In other words, by providing the accommodating hole **355** on the base **35**, an overall design height of the base **35** can be reduced, thereby reducing the overall height size of the camera module **30**.

(227) By way of example but not limitation, a height of the capacitor in the electrical element **312** is 0.38 mm, the height of the accommodating cavity **354** is 0.1 mm, and a thickness of the main body **352** of the base **35** is set to be 0.4 mm, that is, the height of the accommodating hole **355** is 0.4 mm. Thus, when the base **35** is provided on the circuit board **31**, the capacitor in the electrical elements **312** cannot be completely accommodated in the accommodating cavity **354**, accordingly,

an upper end of the capacitor in the electrical elements **312** extends into the accommodating hole **355** and is accommodated in the accommodating hole **355**. It should be understood that in the embodiment of the present application, the accommodating hole **355** should be configured to match the electrical element **312** of the circuit board **31**, a size of the accommodating hole **355** is determined by a horizontal size of the electrical element **312**, that is, the electrical element **312** should be ensured to be accommodated in the accommodating hole **355**.

(228) Further, as shown in FIG. **28**, in the specific example, the base **35** is further provided with a light transmitting hole **356**, wherein the light transmitting hole **356** is formed on the main body **352** of the base **35** and corresponds to the photosensitive chip **32**, and the light transmitting hole **356** is used to place the color filtering element **331**. Accordingly, the main body **352** of the base **35** is further provided with an overhanging arm **357**, wherein the overhanging arm **357** integrally extends on the main body **352** and defines a size of the light transmitting hole **356**, the color filtering element **331** is placed on the overhanging arm **357** and filters light received by the module. It should be specially noted that in the specific example, when the base **35** is provided on the circuit board **31**, then the color filtering element **331** is placed on the overhanging arm **357** of the main body **352**, and an upper end of at least one electrical element **312** is accommodated in the accommodating hole **355**, it can be observed that top surfaces of part of the electrical elements **312** are higher than a bottom surface of the color filtering element **331**.

(229) It is worthwhile to note that in the specific example, the color filtering element **331** can be implemented into different types, which include but are not limited to, an infrared ray cut-off filter, a full-transmittance spectral filter, other filters, and a combination of multiple filters. Specifically, for example, when the color filtering element **331** is implemented as a combination of an infrared ray cut-off filter and a full-transmittance spectral filter, that is, the infrared ray cut-off filter and the full-transmittance spectral filter can be switched to be selectively located on the photosensitive path of the photosensitive chip **32**, and by this way, when the camera module **30** is used in an environment with sufficient amount of light such as daytime, the infrared ray cut-off filter can be switched to the photosensitive path of the photosensitive chip **32** to filter infrared rays in light which is reflected by an object and enters the camera module **30** through the infrared ray cut-off filter. Moreover, when the camera module **30** is used in an environment with dark light such as night, the full-transmittance spectral filter can be switched to the photosensitive path of the photosensitive chip **32** to allow infrared rays in light which is reflected by an object and enters the camera module **30** to be transmitted.

(230) Certainly, the color filtering element **331** can also be provided at another position on the photosensitive path of the photosensitive chip **32**, for example, the color filtering element **331** is provided at a bottom side of the optical lens **332**, or a bottom part of the optical lens **332**, which is not limited in the present application.

(231) Particularly, as shown in FIG. **28**, in the specific example, the base **35** can be implemented as a plastic support, which is pre-prepared and then attached to a top surface of the circuit board **31**, or, the base **35** can be implemented as a molded base, which can be integrally formed and attached to the top surface of the circuit board **31** by an injection molding process. However, due to the limitation of the forming process of the base **35**, the accommodating hole **355** is set to be a through hole, that is, the accommodating hole **355** communicates the accommodating cavity **354** with the external environment. It should be conceivable that when the camera module **30** is assembled, dirt can easily enter via the accommodating hole **355**, causing stains on the photosensitive chip **32**.

(232) Therefore, as shown in FIG. **28**, in the specific example, the camera module **30** further includes a protective piece **38**, wherein the protective piece **38** integrally extends downward from the main body **352**, when the base **35** is provided on the circuit board **31**, the protective piece **38** surrounds a periphery of the photosensitive chip **32**, and the protective piece **38**, the main body **352** of the base **35** and the color filtering element **331** provided on the main body **352** form a sealed space to prevent dirt from entering the photosensitive chip **32**.

(233) In a specific implementation, the protective piece **38** can be implemented as a part of the main body **352** of the base **35**, and integrally extends downward from the main body **352**, wherein when the base **35** is provided on the circuit board **31**, the protective piece **38** surrounds the periphery of the photosensitive chip **32**, and the protective piece **38**, the main body **352** of the base **35** and the color filtering element **331** provided on the main body **352** form the sealed space to prevent dirt from entering the photosensitive chip **32**. Or, the protective piece **38** and the base **35** are provided separately, as shown in FIG. **29**, for example, the protective piece **38** is attached to the base **35** by a process such as an adhering process, thereby reducing the forming difficulty of the base **35**.

(234) Preferably, an upper end of the accommodating hole **355** is further sealed by a film or glue filling, to protect the electrical elements **312** from being damaged on the one hand, and to further enhance the sealing effect to prevent dirt from entering the photosensitive chip **32** on the other hand.

(235) It is worthwhile to note that in the specific example, the camera module **30** can be implemented as a fixed focus module or a dynamic focus module, wherein when the camera module **30** is a dynamic focus module, the camera module **30** further includes a driver **36** (for example, but is not limited to, a motor) electrically connected to the circuit board **31**, and the driver **36** is used to controllably drive the lens to move to realize auto-focus (Auto-Focus), as shown in FIG. **30**.

(236) Particularly, as shown in FIG. **30**, the driver **36** includes at least one positioning pillar **361**, wherein the positioning pillar extends on a lower end of the driver **36**. Moreover, a position where the at least one positioning pillar **361** is formed of the driver **36** corresponds to at least one accommodating hole **355**, so that when the driver **36** is mounted on the base **35**, the positioning pillar is clamped in the accommodating hole **355** in a plug-pin manner. Thus, the mounting accuracy of the driving piece can be improved by cooperation of the positioning pillar **361** and the accommodating hole **355**, and meanwhile, the reliability of the driver **36** can also be improved by the cooperation of the positioning pillar and the accommodating hole **355**.

(237) FIG. **31** is yet another specific example of the camera module **30** according to an embodiment of the present application, wherein the camera module **30** in FIG. **31** is a variant implementation mode of the camera module **30** in FIG. **28**.

(238) Specifically, as shown in FIG. **31**, in the specific example, the protective piece **38** is implemented as a protective film, the protective film is attached to an upper end (a top surface of the main body **352**) of the accommodating hole **355**, so that when the base **35** is provided on the circuit board **31**, the accommodating hole **355** and the accommodating cavity **354** are sealed by the protective film, thereby preventing dirt from entering the photosensitive chip **32**. Moreover, the protective film can also protect the electrical elements **312**. For example, the protective film can be implemented as an attached film, or the protective film is formed on the upper end of the accommodating hole **355** by a process such as a glue filling process, so as to seal the accommodating hole **355**.

(239) FIG. **32** is yet another specific example of the camera module **30** according to an embodiment of the present application, wherein the camera module **30** in FIG. **32** is a variant implementation mode of the camera module **30** in FIG. **28**.

(240) Specifically, as shown in FIG. **32**, in the specific example, the electrical elements **312** provided on the circuit board **31** are provided on two sides of the circuit board **31**, that is, the photosensitive chip **32** is provided on the circuit board **31**, and the electrical elements **312** are located on two sides of the photosensitive chip **32**. Those skilled in the art should know that in the existing camera module, most of the electrical elements **312** on the circuit **31** are arranged at a periphery (or four sides) of the circuit boards **31**.

(241) Further, as shown in FIG. **32**, in the specific example, the protective piece **38** is integrally formed on the main body **352** and extends downward from the main body **352**. Preferably, the

protective piece **38** extends downward from the main body **352** parallel to the side walls **353** to form a receiving cavity **358** between the side walls **353** and the protective piece **38**. Moreover, the accommodating hole **355** is formed between the side walls **353** and the protective piece **38** and communicated with the receiving cavity **358**.

(242) Particularly, as shown in FIG. **32**, in the specific example, the electrical elements **312** are laid at the circuit board **31**, such that when the base **35** is attached to the top surface of the circuit board **31**, the electrical elements **312** are received in the receiving cavity **358**. Moreover, part of the electrical elements **312** which are higher than the receiving cavity **358** can be accommodated in the accommodating hole **355**.

(243) It should be understood that in the specific example, positions of the side walls **353** and the protective piece **38** should be determined according to the layout of the electrical elements **312** on the circuit board **31**. For example, when the electrical elements **312** are distributed on two sides of the circuit board **31** in an array, the protective piece **38** extends downward from the main body **352** parallel to the side walls **353**, and is formed between the electrical elements **312** and the photosensitive chip **32** so as to isolate the photosensitive chip **32** and prevent dirt from entering the photosensitive chip **32** via the accommodating hole **355**.

(244) It is worthwhile to point out that in the specific example, the protective pieces **38** only need to be respectively formed between the photosensitive chip **32** and the electrical elements **312** to isolate the photosensitive chip **32**, that is, the protective pieces **38** do not need to be provided at the periphery of the photosensitive chip **32**, and only need to be formed on two sides of the photosensitive chip **32**. In other words, in the specific example, the camera module **30** has an extreme narrow side, wherein the extreme narrow side is formed on a side, without the electrical component **312**, of the circuit board **31**, and positions for mounting the photosensitive chip **32** and the optical lens **332** are close to edges of the circuit board **31**. Particularly, the extreme narrow side may allow the camera module **30** to be provided on an edge of a smart phone.

(245) FIG. **33** is yet another specific example of the camera module **30** according to an embodiment of the present application. As shown in FIG. **33**, in the specific example, the camera module **30** includes an optical lens **332**, a base **35**, a color filtering element **331**, a photosensitive chip **32**, and a circuit board **31**, wherein the photosensitive chip **32** can be conductively provided on the circuit board **31**, the base **35** is integrally formed on the circuit board **31** by a molding process, the optical lens **332** and the color filtering element **331** are in sequence provided on a photosensitive path of the photosensitive chip **32**, and the base **35** is used to support the color filtering element **331**. Thus, imaging light passing through the display screen **20** first reaches the optical lens **332**, then is filtered by the color filtering element **331**, and reaches the photosensitive chip **32** to be sensed by the photosensitive chip **32** to perform an imaging reaction.

(246) Particularly, the specific example is an optimized solution of the existing molding process-based camera module. Those skilled in the art should know that in the existing molding process-based camera module, generally a photosensitive chip and electrical elements are first attached to a circuit board, then a molded base is formed on the circuit board by a molding process, a filter is attached to a back side of the lens base, and a lens is attached to the filtering component to keep the lens on a photosensitive path of the chip, as shown in FIG. **34**. The assembly method in the prior art greatly limits the height of the camera module.

(247) In detail, although the horizontal size and height of the camera module can be reduced by replacing a conventional lens base with the molded base, a mold used in the molding process needs to avoid the electrical elements (especially the capacitor with a large size, at present, a height of the smallest capacitor is 0.38 mm) such as capacitors and resistors on the circuit board, a certain safe distance further needs to be reversed between the mold and each electrical element, and therefore, a height of the molded base needs to be at least greater than 0.4 mm. On the other hand, usually the filter and a supporting piece are combined to form a filtering component, and then the filtering component is attached to the molded base, because the supporting piece is usually formed by an

injection molding process, which requires a thickness of a part for supporting the filter of the supporting piece to be basically greater than 0.15 mm, and a thickness of the filter itself is usually greater than 0.21 mm, and therefore, a thickness of the filtering component needs to be at least greater than 0.36 mm.

(248) That is, a distance between the lens and the circuit board **31** is equal to the sum of the height of the molded base and the thickness of the filtering component (greater than 0.76 mm), and due to the limitations of the above factors, the distance between the lens and the circuit board **31** in the existing camera module cannot further be reduced, that is, the height of the existing camera module cannot be further reduced, thereby failing to meet the market demand for thinness and miniaturization of camera modules.

(249) Accordingly, as shown in FIG. **33**, in the specific example, the molded base is provided with a recessed step part used to mount the color filtering element **331**. That is, compared with the existing molding process-based camera module, in the specific example, a top surface of the molded base is a non-flat surface which is provided with a recessed step part. Accordingly, by mounting the color filtering element **331** on the recessed step part of the molded base, a supporting piece of the color filtering element can be omitted, and a distance between the color filtering element **331** and the circuit **31** can be reduced, thereby reducing the height of the module.

(250) Specifically, as shown in FIG. **33**, in the specific example, the molded base is provided with a stepped peripheral groove **350**, wherein the color filtering element **331** of the light transmitting component **33** is provided in the stepped peripheral groove **350** of the molded base. By this way, the distance between the optical lens **332** and the circuit board **31** is no longer limited by the thickness of the color filtering element **331** itself, that is, the distance between the optical lens **332** and the circuit board **31** can be reduced to be smaller than the sum of the thickness of the color filtering element **331** and the height of the molded base, thereby reducing the overall height size of the camera module **30**.

(251) FIG. **35** is yet another specific implementation mode of the camera module **30** according to an embodiment of the present application. As shown in FIG. **35**, in the specific example, the camera module **30** is optimized from the perspective of the structure of the photosensitive chip itself, so as to reduce the overall height size of the camera module **30**. In other words, in the specific implementation mode, the camera module **30** can be implemented as the camera module and the variant implementation mode thereof in any one of FIG. **21** to FIG. **33**.

(252) Specifically, in the specific example, in the camera module **30**, a photosensitive chip **32A** with a quantum dot thin film **323A** is used to replace the conventional CMOS/CCD photosensitive chip. Compared with the conventional CMOS/CCD photosensitive chip, the photosensitive chip **32A** with the quantum dot thin film **323A** has advantages in terms of plan view size and height size. First, with adoption of the photosensitive chip **32A** with the quantum dot thin film **323A**, a size in a Z axial direction of the photosensitive chip can be reduced. As shown in FIG. **35**, the photosensitive chip **32A** with the quantum dot thin film **323A** includes a color filter **321A**, a top electrode **322A**, the quantum dot thin film **323A**, a bottom electrode **324A**, and a pixel circuit **325A** from top to bottom, wherein the top electrode **322A**, the quantum dot thin film **323A**, the bottom electrode **324A** constitute a photosensitive layer of the photosensitive chip **32A** with the quantum dot thin film **323A**, the quantum dot thin film **323A** is electrically connected to the two electrodes, a current and/or a voltage between the two electrodes is related to an intensity of light received by the quantum dot thin film **323A**, and the pixel circuit **325A** includes a charge storage and reading circuit. Particularly, the color filter can be implemented as a Bayer filter or Mono filter, which is not limited in the present application.

(253) During operation, light passing through the color filter **321A** is irradiated on the photosensitive layer, the photosensitive layer generates a charge between the top electrode and the bottom electrode at a given bias voltage, so that the voltage is accumulated in the charge storage in an integration period, the pixel circuit **325A** reads an electrical signal and transmits the same to the

chip, wherein the electrical signal is a signal reflecting an intensity of light absorbed by the photosensitive layer in the integration period, the electrical signal is an light intensity generated by the light passing through the color filter **321A**, and therefore, the electrical signal can correspond to the light passing through the color filter **321A**, that is, if the color filter **321A** is red, which indicates that only red light can be transmitted, an electrical signal generated by the corresponding photosensitive layer below the color filter **321A** represents an intensity of red light in light at the position.

(254) Compared with the existing CMOS or CCD chip, the photosensitive chip **32A** with the quantum dot thin film **323A** has a relatively small thickness size.

(255) FIG. **36** is yet another specific example of the photosensitive chip of the camera module **30** according to an embodiment of the present application, wherein the photosensitive chip in FIG. **36** is a variant implementation mode of the photosensitive chip in FIG. **35**.

(256) Specifically, as shown in FIG. **36**, in the specific example, the quantum dot thin film **323A** of the photosensitive layer is configured to correspond to light of a selected color or group of colors, for example, a color sensitive pixel can be formed by combining a photoconductive material and a wavelength selective absorption material (such as a material for forming the color filter **321A** array) to realize the color sensitivity. Accordingly, the quantum dot thin film **323A** can be configured to be sensitive to three colors of red (R), green (G), and blue (B), respectively. Thus, the color filter **321A** in the photosensitive chip can be directly omitted.

(257) During operation, when the light passes through the color sensitive pixel, the sensitive pixel will absorb corresponding light, and an intensity of the light of the wavelength or wave band is converted into an electric signal which is transmitted to the chip by the pixel circuit **325A** for imaging, and the rest of light continues to be transmitted forward and does not affect the photoelectric conversion of the pixel point. Accordingly, with the technical solution, not only the size in the Z direction of the photosensitive chip can be reduced, but also the photosensitive chip can receive larger amount of light without light filtering of the color filter **321A**, and thus, the imaging of the photosensitive chip is clearer.

(258) Further, with adoption of the photosensitive chip **32A** with the quantum dot thin film **323A**, sizes in X and Y axial directions of the photosensitive chip can be reduced. Specifically, due to the high light transmittance of the quantum dot thin film **323A**, after being configured as a material which is sensitive to light of a certain wavelength or wave band, the quantum dot thin film **323A** can only absorb corresponding light, and other light will pass through the thin film and continues to be transmitted forward. Therefore, a plurality of quantum dot thin films **323A** sensitive to light of a certain wavelength or wave band can be arranged vertically.

(259) In other words, the intensity information of light of multiple wavelengths or wave bands can be obtained at the same time at a pixel point position. For example, three kinds of quantum dot thin films **323** of a red sensitive pixel, a green sensitive pixel, and a blue sensitive pixel are arranged vertically, when light passes through the red sensitive pixel, red light is absorbed and converted into an electrical signal, the rest of light continues to be transmitted forward, when the light passes through the green sensitive pixel, green light is absorbed and converted into an electrical signal, the rest of light continues to be transmitted forward, when the light passes through the blue sensitive pixel, blue light is absorbed and converted into an electrical signal. Therefore, the intensity information of light of multiple wavelengths or wave bands can be obtained at the same time at a pixel-sized point.

(260) It worthwhile to note that the RGB color described in the specific example of the present application is not limitative, each quantum dot thin film **323A** can absorb and covert any light as required, and the quantum dot thin film **323A** only needs to be configured to be sensitive to light as required.

(261) Moreover, in the specific example, because the conventional color filter **321A** is not used, not only a higher light intensity can be obtained, but also a higher resolution can be obtained for the

photosensitive chip of the same specification. In other words, at the same resolution, by the method of the present solution, the sizes in the X and Y directions of the photosensitive chip can be reduced, thereby further reducing the plan view size of the camera module **30**.

(262) Moreover, the quantum dot thin film **323A** in the chip with the quantum dot thin film **323A** of the present application can be prepared by the following process.

(263) In a forming manner, a quantum dot material is processed by molten pool casting to form the quantum dot thin film **323A**. The molten pool casting may include steps of depositing the measured quantum dot material on a substrate and allowing a solution to evaporate, wherein the formed film may be or may not be cracked.

(264) In a forming manner, a quantum dot material is processed by electro-deposition to form the quantum dot thin film **323A**.

(265) In a forming manner, a quantum dot material is processed by vapor deposition to form the quantum dot thin film **323A**.

(266) In a forming manner, a quantum dot material is processed by spraying of a spray gun to form the quantum dot thin film **323A**. The spraying of the spray gun may include a processing from gap. The spraying of the spray gun may include an entrainment in a solvent.

(267) In a forming manner, a quantum dot material is processed by growth from a solution to form the quantum dot thin film **323A**. The growth of the film from the solution may include cross-linking. A cross-linking agent can be attached to at least part of a substrate to cross-link quantum dots. When the substrate attached with the cross-linking agent is immersed in a quantum dot solution, quantum dots can become cross-linked and grow at a position where the cross-linking agent is attached of the substrate, and the growth process can be similar to the growth process of a seed crystal. Because the growth occurs at the position where the cross-linking agent is attached, the forming of a patterned film on the substrate can be realized by depositing a cross-linking agent along a patterned substrate.

(268) In a forming manner, a quantum dot material is processed by a draining system to form the film. The draining system can enable a single layer of quantum dot thin film **323A** capable of depositing quantum dots to be deposited in a pattern.

(269) In a forming manner, a quantum dot material is processed by accelerating or evaporating in a gas phase to form the quantum dot thin film **323A**.

(270) In a forming manner, a quantum dot material is processed by a screen-printing method to form the quantum dot thin film **323A**.

(271) In a forming manner, a quantum dot material is processed by an ink-jet printing method to form the quantum dot thin film **323A**.

(272) In conclusion, the camera module **30** provided below the display screen can adopt but is not limited to the above technical solutions and variant implementation modes thereof, so that the height size of the camera module **30** can be reduced, thereby meeting the requirements of thin smart phones.

(273) Those skilled in the art should understand that the above description and the embodiments of the present invention shown in the drawings are only examples and are not intended to limit the present invention. The objectives of the present invention are completely and effectively realized. The functions and structural principles of the present invention are shown and described in the embodiments, and any variation or modification may be made to the implementation modes of the present invention without departing from the principles described.

Claims

1. A display screen, characterized by comprising: a cover plate layer (**21**), a touch layer (**22**), a polarizing layer (**23**), an encapsulation layer (**24**), a pixel layer (**25**), and a circuit driving layer (**26**) from top to bottom, wherein the circuit driving layer (**26**) is formed on a bottom side of the pixel

layer (25), and is electrically connected to the pixel layer (25) to drive the pixel layer (25) to operate; the encapsulation layer (24) is formed on a top side of the pixel layer (25) to encapsulate the pixel layer (25); the pixel layer (25) includes a non-light transmitting area defined by pixels and a light transmitting area defined by gaps between the pixels, and the pixels, which have a low light resistance rate, are distributed in an array, and the gaps, which have a high light resistance rate and are filled with a completely different material than the material of the pixels, are reserved in spaces between various pixels to allow light passing through the cover plate layer (21), the touch layer (22), the polarizing layer (23) and the encapsulation layer (24) in sequence to pass through the pixel layer (25) via the gaps; and the display screen further includes a microlens layer provided above the pixel layer (25), the microlens layer corresponds to each gap between the pixels in the pixel layer (25), and is used to converge light to each gap before the light passes through the pixel layer (25) via the gaps so as to increase the light transmittance of the display screen.

2. The display screen according to claim 1, wherein the microlens layer includes microlens units distributed in an array, and each microlens unit respectively corresponds to each gap.

3. The display screen according to claim 2, wherein the microlens units of the microlens layer are integrally formed in the gaps between the pixels in the pixel layer (25), and the encapsulation layer (24) is integrally formed on the microlens layer and the pixel layer (25) to encapsulate the pixel layer (25) and the microlens layer.

4. The display screen according to claim 3, wherein the microlens layer is integrally formed on a top surface of the encapsulation layer (24) in a protruded manner or a recessed manner.

5. The display screen according to claim 2, wherein a height size of the microlens unit is smaller than or equal to that of the encapsulation layer (24).

6. The display screen according to claim 2, wherein a horizontal size of the microlens unit is larger than a size of the gap.

7. The display screen according to claim 2, wherein a longitudinal size of the microlens unit is larger than or equal to a size of a gap between adjacent pixels.

8. The display screen according to claim 2, wherein a refractive index of a material for forming the microlens layer is higher than that of a material for forming the encapsulation layer (24).

9. The display screen according to claim 1, wherein the material for forming the encapsulation layer (24) is a light-transmissive rigid material or a light-transmissive flexible material.

10. The display screen according to claim 1, further including a back plate layer (27) having an opening hole, wherein the opening hole corresponds to the gaps between the pixels in the pixel layer (25).

11. The display screen according to claim 2, wherein the microlens unit includes a film structure, and light is converged after passing through the film structure.

12. The display screen according to claim 11, wherein the film structure is formed on a recessed bottom surface of the encapsulation layer (24).

13. The display screen according to claim 11, wherein the film structure is formed on a recessed bottom surface of the polarizing layer (23).

14. A preparation method of a display screen, characterized by comprising: forming a microlens layer on a pixel layer (25) of the display screen, wherein microlens units of the microlens layer correspond to gaps between various pixels in the pixel layer (25), wherein a circuit driving layer (26) is provided on a bottom side of the pixel layer (25), and the circuit driving layer (26) is electrically connected to the pixel layer (25) to drive the pixel layer (25) to operate; and forming an encapsulation layer (24) on the microlens layer and the pixel layer (25) to encapsulate the microlens layer and the pixel layer (25) through the encapsulation layer (24), wherein the encapsulation layer (24) is further provided thereon with a polarizing layer (23), a touch layer (22) and a cover plate layer (21) in sequence, wherein the pixel layer (25) includes a non-light transmitting area defined by the pixels and a light transmitting area defined by the gaps between the pixels, and the pixels, which have a low light resistance rate, are distributed in an array, and the

gaps, which have a high light resistance rate and are filled with a completely different material than the material of the pixels, are reserved in spaces between various pixels to allow light passing through the cover plate layer (21), the touch layer (22), the polarizing layer (23) and the encapsulation layer (24) in sequence to pass through the pixel layer (25) via the gaps.

15. The preparation method of the display screen according to claim 14, wherein the microlens units of the microlens layer are integrally formed in the gaps between various pixels in the pixel layer (25).

16. The preparation method of the display screen according to claim 15, wherein the encapsulation layer (24) is integrally formed on the microlens layer and the pixel layer (25) by a deposition process.

17. The preparation method of the display screen according to claim 14, wherein a refractive index of a material for forming the microlens layer is higher than that of a material for forming the encapsulation layer (24).

18. A preparation method of a display screen, characterized by comprising: integrally forming a microlens layer on an encapsulation layer (24); providing the encapsulation layer (24) above a pixel layer (25), wherein microlens units of the microlens layer correspond to gaps between various pixels in the pixel layer (25), wherein a circuit driving layer (26) is provided on a bottom side of the pixel layer (25), and the circuit driving layer (26) is electrically connected to the pixel layer (25) to drive the pixel layer (25) to operate; and providing a polarizing layer (23), a touch layer (22) and a cover plate layer (21) in sequence on the encapsulation layer (24), wherein the pixel layer (25) includes a non-light transmitting area defined by the pixels and a light transmitting area defined by the gaps between the pixels, and the pixels, which have a low light resistance rate, are distributed in an array, and the gaps, which have a high light resistance rate and are filled with a completely different material than the material of the pixels, are reserved in spaces between various pixels to allow light passing through the cover plate layer (21), the touch layer (22), the polarizing layer (23) and the encapsulation layer (24) in sequence to pass through the pixel layer (25) via the gaps.

19. The preparation method of the display screen according to claim 18, wherein the microlens layer is integrally formed on a top surface of the encapsulation layer (24) in a protruded manner or a recessed manner.

20. The preparation method of the display screen according to claim 18, wherein a refractive index of a material for forming the microlens layer is higher than that of a material for forming the encapsulation layer (24).
