

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250278361

Kind Code

A1

Publication Date

September 04, 2025

Inventor(s)

JANG; Min Jun et al.

MEMORY SYSTEM, MEMORY CONTROLLER, AND METHOD FOR OPERATING SAME

Abstract

Embodiments of the present disclosure relate to a memory system, a memory controller, and a method for operating the same. Garbage collection is performed with regard to the memory device on the basis of a first amount of time and a second amount of time, the first amount of time being a period of time between triggering of first garbage collection and triggering of second garbage collection, and the second amount of time being an amount of time necessary to perform the second garbage collection. A ratio of the first amount of time to the second amount of time is determined as a target ratio value, and the second amount of time is determined to be equal to or longer than a minimum garbage collection operation time. Accordingly, efficient garbage collection can be performed, and the optimal time to perform garbage collection can be determined with regard to a configured performance drop value.

Inventors: JANG; Min Jun (Gyeonggi-do, KR), CHOI; Hyung Pil (Gyeonggi-do, KR)

Applicant: SK hynix Inc. (Gyeonggi-do, KR)

Family ID: 75973967

Appl. No.: 19/212687

Filed: May 20, 2025

Foreign Application Priority Data

KR 10-2019-0153987

Nov. 27, 2019

Related U.S. Application Data

parent US continuation 18176935 20230301 parent-grant-document US 12332778 child US 19212687

Publication Classification

Int. Cl.: **G06F12/02** (20060101); **G06F11/30** (20060101); **G06F12/06** (20060101); **G06F13/16** (20060101)

U.S. Cl.:

CPC **G06F12/0246** (20130101); **G06F12/0253** (20130101); G06F11/3037 (20130101); G06F12/0646 (20130101); G06F13/1689 (20130101); G06F2212/1016 (20130101); G06F2212/7205 (20130101)

Background/Summary

CROSS REFERENCE TO RELATED APPLICATION [0001] This application is a continuation of U.S. patent application Ser. No. 18/176,935 filed on Mar. 1, 2023, which is a continuation application of U.S. patent application Ser. No. 16/891,314 filed on Jun. 3, 2020, and issued as U.S. Pat. No. 11,630,764 on Apr. 18, 2023, which claims priority from Korean Patent Application No. 10-2019-0153987, filed on Nov. 27, 2019, which is hereby incorporated by reference for all purposes as if fully set forth herein.

BACKGROUND OF THE INVENTION

1. Field of the Invention

[0002] Embodiments of the present disclosure relate to a memory system, a memory controller, and a method for operating the same.

2. Description of the Prior Art

[0003] A memory system, e.g., a storage device, stores data on the basis of a request of a host such as a computer, a mobile terminal (for example, a smartphone or a tablet), or other kinds of electronic devices. The memory system may include not only a device configured to store data in a magnetic disk, such as a hard disk drive (HDD), but also a device configured to store data in a nonvolatile memory, such as a solid state drive (SSD), a universal flash storage (UFS) device, and an embedded MMC (eMMC) device.

[0004] The memory system may further include a memory controller for controlling the memory device (for example, volatile memory/nonvolatile memory). The memory controller may receive a command input from the host and may perform or control operations for reading, writing, or erasing data in the memory device included in the memory system on the basis of the received command. In addition, the memory controller may drive firmware for performing a logical operation for performing or controlling such operations.

[0005] The memory controller may perform garbage collection with regard to the memory device, in order to secure additional free memory blocks, if the number of free memory blocks in the memory device becomes insufficient in the course of repeatedly writing data in the memory device.

SUMMARY OF THE INVENTION

[0006] Embodiments of the present disclosure may provide a memory system, a memory controller, and a method for operating the same, wherein garbage collection can be performed efficiently.

[0007] In addition, embodiments of the present disclosure may provide a memory system, a memory controller, and a method for operating the same, wherein the optimal time to perform garbage collection can be determined with regard to a configured performance drop value.

[0008] In an aspect, embodiments of the present disclosure may provide a memory system including a memory device and a memory controller configured to control the memory device.

[0009] The memory controller may perform garbage collection with regard to the memory device on the basis of a first amount of time and a second amount of time, the first amount of time being a period of time between triggering of first garbage collection and triggering of second garbage collection, and the second amount of time being an amount of time necessary to perform the second garbage collection.

[0010] The memory controller may determine a ratio of the second amount of time against the first amount of time as a target ratio value, and may determine the second amount of time to be equal to or longer than a minimum garbage collection operation time.

[0011] The memory controller may determine the first amount of time on the basis of a time at which the total sum of the size of user data written in the memory device, since triggering of the first garbage collection, becomes equal to or greater than a threshold.

[0012] The memory controller may determine the second amount of time on the basis of a performance drop value.

[0013] For example, the memory controller may determine a first data size, which is a size of data written in the memory device when the second garbage collection is performed. The memory controller may determine the first data size on the basis of i) the performance drop value and ii) a second data size, which is the total sum of the size of user data written in the memory device since the first garbage collection is triggered.

[0014] The memory controller may determine the second amount of time on the basis of a value obtained by dividing the first data size by a number of partial programs that can be programmed in the memory device per a set amount of time.

[0015] As another example, the memory controller may determine the second amount of time on the basis of i) a performance drop value and ii) a read time, which is an amount of time spent to perform a user data reading operation since the first garbage collection is triggered.

[0016] In another aspect, embodiments of the present disclosure may provide a memory controller including: a memory interface configured to communicate with a memory device; and a control circuit configured to control the memory device.

[0017] The control circuit may perform garbage collection with regard to the memory device on the basis of a first amount of time and a second amount of time, the first amount of time being a period of time between triggering of first garbage collection and triggering of second garbage collection, and the second amount of time being an amount of time necessary to perform the second garbage collection.

[0018] The control circuit may determine a ratio of the second amount of time against the first amount of time as a target ratio value, and may determine the second amount of time to be equal to or longer than a minimum garbage collection operation time.

[0019] The control circuit may determine the first amount of time on the basis of a time at which the total sum of the size of user data written in the memory device, since triggering of the first garbage collection, becomes equal to or greater than a threshold.

[0020] The control circuit may determine the second amount of time on the basis of a performance drop value.

[0021] For example, the control circuit may determine a first data size, which is a size of data written in the memory device when the second garbage collection is performed. The control circuit may determine the first data size on the basis of i) the performance drop value and ii) a second data size, which is the total sum of the size of user data written in the memory device since the first garbage collection is triggered.

[0022] As another example, the control circuit may determine the second amount of time on the basis of i) a performance drop value and ii) a read time, which is an amount of time spent to perform a user data reading operation since the first garbage collection is triggered.

[0023] In another aspect, embodiments of the present disclosure may provide a method for operating a memory controller.

[0024] A method for operating a memory controller may include a step of determining a first amount of time, which is a period of time between triggering of first garbage collection and triggering of second garbage collection.

[0025] The method for operating a memory controller may include a step of determining a second amount of time, which is an amount of time necessary to perform the second garbage collection.

[0026] The method for operating a memory controller may include a step of performing garbage collection with regard to the memory device on the basis of the first amount of time and the second amount of time. A ratio of the second amount of time against the first amount of time may be determined as a target ratio value, and the second amount of time may be determined to be equal to or longer than a minimum garbage collection operation time.

[0027] In another aspect, embodiments of the present disclosure may provide an operating method of a controller.

[0028] The operating method of a controller may include a step of determining a minimum operation time for a subsequent of two time-adjacent garbage collection operations based on an amount of data to be processed, a performance drop value and a number of partial programs performed in a set amount of time.

[0029] The operating method of a controller may include a step of controlling a memory device to perform the garbage collection operations according to a target ratio based on the minimum operation time.

[0030] The period between two time-adjacent garbage collection operations enables the controller to control the memory device to process the amount of data in response to requests from a host.

[0031] According to embodiments of the present disclosure, garbage collection can be performed efficiently.

[0032] In addition, according to embodiments of the present disclosure, the optimal time to perform garbage collection can be determined with regard to a configured performance drop value.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0033] The above and other aspects, features and advantages of the present disclosure will be more apparent from the following detailed description taken in conjunction with the accompanying drawings, in which:

[0034] FIG. 1 is a schematic diagram illustrating a configuration of a memory system according to an embodiment of the present disclosure;

[0035] FIG. 2 is a block diagram schematically illustrating a memory device according to an embodiment of the present disclosure;

[0036] FIG. 3 is a diagram schematically illustrating respective memory blocks of a memory device according to an embodiment of the present disclosure;

[0037] FIG. 4 is a diagram illustrating the structure of word lines and bit lines of a memory device according to an embodiment of the present disclosure;

[0038] FIG. 5 is a timing diagram regarding operations of a memory system according to an embodiment of the present disclosure;

[0039] FIG. 6 is a diagram illustrating a criterion used by a memory system according to an embodiment of the present disclosure to determine a first amount of time and a second amount of time;

[0040] FIG. 7 is a diagram illustrating an example of determining the first amount of time in a memory system according to an embodiment of the present disclosure;

[0041] FIG. **8** is a diagram illustrating an example of determining the second amount of time in a memory system according to an embodiment of the present disclosure;

[0042] FIG. **9** is a diagram illustrating an example of determining a first data size in order to determine the second amount of time in a memory system according to an embodiment of the present disclosure;

[0043] FIG. **10** is a diagram illustrating another example of determining the second amount of time in a memory system according to an embodiment of the present disclosure;

[0044] FIG. **11** is a diagram illustrating a method for operating a memory controller according to an embodiment of the present disclosure;

[0045] FIG. **12** is a flowchart illustrating a method for determining the second amount of time in a memory system according to an embodiment of the present disclosure; and

[0046] FIG. **13** is a diagram illustrating a configuration of a computing system according to an embodiment of the present disclosure.

DETAILED DESCRIPTION

[0047] Hereinafter, embodiments of the present disclosure are described in detail with reference to the accompanying drawings. Throughout the specification, reference to “an embodiment,” “another embodiment” or the like is not necessarily to only one embodiment, and different references to any such phrase are not necessarily to the same embodiment(s).

[0048] FIG. **1** is a diagram illustrating a schematic configuration of a memory system **100** according to an embodiment of the present disclosure.

[0049] Referring to FIG. **1**, the memory system **100** may include a memory device **110** configured to store data, a memory controller **120** configured to control the memory device **110**, and the like.

[0050] The memory device **110** includes multiple memory blocks and operates in response to control of the memory device **120**. Operations of the memory device **110** may include, for example, a read operation, a program operation (also referred to as “write operation”), an erasure operation, and the like.

[0051] The memory device **110** may include a memory cell array including multiple memory cells (also simply referred to as “cell”) configured to store data. The memory cell array may exist in a memory block.

[0052] The memory device **110** may be implemented as any of various types of memories, such as a double data rate synchronous dynamic random access memory (DDR SDRAM), a low power double data rate4 (LPDDR4) SDRAM, a graphics double data rate (GDDR) SDRAM, a low power DDR (LPDDR), a Rambus dynamic random access memory (RDRAM), a NAND flash memory, a 3D NAND flash memory, a NOR flash memory, a resistive random access memory (RRAM), a phase-change memory (PRAM), a magnetoresistive random access memory (MRAM), a ferroelectric random access memory (FRAM), or a spin transfer torque random access memory (STT-RAM).

[0053] The memory device **110** may be implemented in a three-dimensional array structure. Embodiments of the present disclosure are applicable not only to a flash memory device having a charge storage layer configured by a conductive floating gate, but also to a charge trap flash (CTF) having a charge storage layer configured by an insulating film.

[0054] The memory device **110** is configured to receive a command, an address, and the like from the memory controller **120** and to access an area selected by the address inside the memory cell array. That is, the memory device **110** may perform an operation corresponding to the command with regard to the area selected by the address.

[0055] For example, the memory device **110** may perform a program operation, a read operation, an erasure operation, and the like. In relation thereto, during a program operation, the memory device **110** may program data in an area selected by an address. During a read operation, the memory device **110** may read data from an area selected by an address. During an erasure operation, the memory device **110** may erase data stored in an area selected by an address.

[0056] The memory controller **120** may control a write (program) operation, a read operation, an erasure operation, and a background operation regarding the memory device **110**. The background operation may include a garbage collection (GC) operation, a wear leveling (WL) operation, and/or a bad block management (BBM) operation.

[0057] The memory controller **120** may control operations of the memory device **110** at the request of a host (HOST). Alternatively, the memory controller **120** may control operations of the memory device **110** regardless of the request of the host.

[0058] The memory controller **120** and the host may be separate devices. In another embodiment, the memory controller **120** and the host may be integrated into and implemented as a single device. By way of example, features and aspects of the present invention are described below in the context in which the memory controller **120** and the host are separate devices.

[0059] Referring to FIG. **1**, the memory controller **120** may include a memory interface **122**, a control circuit **123**, and a host interface **121**.

[0060] The host interface **121** is configured to provide an interface for communicating with the host.

[0061] When receiving a command from the host, the control circuit **123** may perform operations of receiving the command through the host interface **121** and processing the received command.

[0062] The memory interface **122** is connected to the memory device **110** and is configured to provide an interface for communicating with the memory device **110**. That is, the memory interface **122** may be configured to provide an interface between the memory device **110** and the memory controller **120** in response to control of the control circuit **123**.

[0063] The control circuit **123** is configured to control overall operation of the memory controller **120**, thereby controlling operations of the memory device **110**. To this end, the control circuit **123** may include, for example, a processor **124** and/or a working memory **124**, and may further include an error detection-and-correction circuit (ECC circuit) **126**, if necessary.

[0064] The processor **124** may control overall operation of the memory controller **120** and may perform logical operations. The processor **124** may communicate with the host through the host interface **121** and may communicate with the memory device **110** through the memory interface **122**.

[0065] The processor **124** may perform the function of a flash translation layer (FTL). The processor **124** may convert a logical block address (LBA) provided by the host to a physical block address (PBA) through the FTL. The FTL may receive the LBA and convert the same to the PBA by using a mapping table.

[0066] The FTL may map addresses in various methods, depending on the mapping unit. Typical address mapping methods include a page mapping method, a block mapping method, and a hybrid mapping method.

[0067] The processor **124** is configured to randomize data received from the host. For example, the processor **124** may randomize data received from the host by using a randomizing seed. The randomized data is provided to the memory device **110** as data to be stored, and is programmed in the memory cell array.

[0068] The processor **124** is configured to derandomize data received from the memory device **110** during a read operation. For example, the processor **124** may derandomize data received from the memory device **110** by using a derandomizing seed. The derandomized data may be output to the host.

[0069] The processor **124** may execute firmware so as to control operations of the memory controller **120**. In other words, the processor **124** may control overall operation of the memory controller **120** and may execute (drive) firmware loaded into the working memory **125** during booting, in order to perform a logical operation.

[0070] The firmware may be a program executed inside the memory system **100**, and may include various functional layers.

[0071] For example, the firmware may include at least one selected from a flash translation layer (FTL) configured to translate between a logical address that the host HOS requests the memory system **100** to provide and a physical address of the memory device **110**, a host interface layer (HIL) configured to interpret a command that the host requests the memory system **100** (storage device) to follow and to deliver the same to the FTL, and a flash interface layer (FIL) configured to deliver a command issued by the FTL to the memory device **110**.

[0072] The firmware may be stored in the memory device **110**, for example, and then loaded into the working memory **125**.

[0073] The working memory **125** may store firmware, program codes, commands, or data necessary to drive the memory controller **120**. The working memory **125** may include, as a volatile memory, a static RAM (SRAM), a dynamic RAM (DRAM), and/or a synchronous DRAM (SDRAM), for example.

[0074] The error detection-and-correction circuit **126** may be configured to detect an error bit of checking target data by using an error correction code and to correct the detected error bit. The checking target data may be, for example, data stored in the working memory **125** or data retrieved from the memory device **110**.

[0075] The error detection-and-correction circuit **126** may be implemented to decode data by using the error correction code. The error detection-and-correction circuit **126** may be implemented by various code decoders. For example, a decoder configured to perform unsystematic code decoding or a decoder configured to perform systematic code decoding may be used.

[0076] For example, the error detection-and-correction circuit **126** may detect error bits, sector by sector, with regard to respective pieces of read data. That is, each piece of read data may include multiple sectors. A sector may refer to a data unit smaller than a page, which is the read unit of a flash memory. Sectors constituting each piece of read data may correspond to each other via addresses.

[0077] The error detection-and-correction circuit **126** may calculate a bit error rate (BER) and determine whether or not each sector is correctable. For example, if the BER is higher than a reference value, the error detection-and-correction circuit **126** may determine that the corresponding sector is uncorrectable (or has failed). On the other hand, if the BER is lower than the reference value, the error detection-and-correction circuit **126** may determine that the corresponding sector is correctable (or has passed).

[0078] The error detection-and-correction circuit **126** may successively perform error detection and correction operations with regard to all pieces of read data. If a sector included in read data is correctable, the error detection-and-correction circuit **126** may omit the error detection and correction operations regarding the corresponding sector with regard to the next piece of read data. After the error detection correction operations are finished with regard to all pieces of read data in this manner, the error detection-and-correction circuit **126** may detect a sector deemed uncorrectable to the end. There may be one or more sectors deemed uncorrectable. The error detection-and-correction circuit **126** may deliver information (for example, address information) regarding the sector deemed uncorrectable to the processor **124**.

[0079] The bus **127** may be configured to provide a channel between the components **121**, **122**, **124**, **125**, and **126** of the memory controller **120**. The bus **127** may include, for example, a control bus for delivering various kinds of control signals and commands and a data bus for delivering various kinds of data.

[0080] The memory controller **120** and the above-mentioned components **121**, **122**, **124**, **125**, and **126** represents an example configuration. In other configurations, one or more of these components may be omitted, and/or one or more components may be integrated into a single component. Of course, the memory controller **120** may include one or more additional components.

[0081] Hereinafter, the memory device **110** is described in more detail with reference to FIG. 2.

[0082] FIG. 2 is a block diagram schematically illustrating a memory device **110** according to an

embodiment of the present disclosure.

[0083] Referring to FIG. 2, the memory device **110** may include a memory cell array **210**, an address decoder **220**, a read-and-write circuit **230**, control logic **240**, a voltage generation circuit **250**, and the like.

[0084] The memory cell array **210** may include multiple memory blocks BLK1-BLKz (z is a natural number equal to or larger than 2).

[0085] In the multiple memory blocks BLK1-BLKz, multiple word lines WL and multiple bit lines BL may be disposed, and multiple memory cells MC may be arranged therein.

[0086] The multiple memory blocks BLK1-BLKz may be connected to the address decoder **220** through the multiple word lines WL. The multiple memory blocks BLK1-BLKz may be connected to the read-and-write circuit **230** through the multiple bit lines BL.

[0087] Each of the multiple memory blocks BLK1-BLKz may include multiple memory cells. For example, the multiple memory cells may be nonvolatile memory cells, and may include nonvolatile memory cells having a vertical channel structure.

[0088] The memory cell array **210** may be configured as a two-dimensional structure, or a three-dimensional structure.

[0089] Each of the multiple memory cells included in the memory cell array **210** may store at least one bit of data. For example, each of the multiple memory cells included in the memory cell array **210** may be a single-level cell (SLC) configured to store one bit of data, a multi-level cell (MLC) configured to store two bits of data, a triple-level cell (TLC) configured to store three bits of data, or a quad-level cell (QLC) configured to store four bits of data. As another example, the memory cell array **210** may include multiple memory cells each configured to store at least five bits of data.

[0090] Referring to FIG. 2, the address decoder **220**, the read-and-write circuit **230**, the control logic **240**, the voltage generation circuit **250**, and the like may operate as peripheral circuits configured to drive the memory cell array **210**.

[0091] The address decoder **220** may be connected to the memory cell array **210** through multiple word lines WL.

[0092] The address decoder **220** may be configured to operate in response to control of the control logic **240**.

[0093] The address decoder **220** may receive addresses through an input/output buffer inside the memory device **110**. The address decoder **220** may be configured to decode a block address among the received addresses. The address decoder **220** may select at least one memory block according to the decoded block address.

[0094] The address decoder **220** may receive a read voltage Vread and a pass voltage Vpass from the voltage generation circuit **250**.

[0095] In the case of a read voltage applying operation during a read operation, the address decoder **220** may apply a read voltage Vread to a selected word line WL inside a selected memory block, and may apply a pass voltage Vpass to the remaining unselected word lines WL.

[0096] During a program verification operation, the address decoder **220** may apply a verification voltage generated by the voltage generation circuit **250** to the selected word line WL inside the selected memory block, and may apply a pass voltage Vpass to the remaining unselected word lines WL.

[0097] The address decoder **220** may be configured to decode a column address among received addresses. The address decoder **220** may transmit the decoded column address to the read-and-write circuit **230**.

[0098] The read operation and program operation of the memory device **110** may be performed page by page. Addresses received when the read operation and program operation are requested may include a block address, a row address, and/or a column address.

[0099] The address decoder **220** may select one memory block and one word line according to the block address and the row address. The column address may be decoded by the address decoder

220 and provided to the read-and-write circuit **230**.

[0100] The address decoder **220** may include a block decoder, a row decoder, a column decoder, and/or an address buffer.

[0101] The read-and-write circuit **230** may include multiple page buffers PB. The read-and-write circuit **230** may operate as a “read circuit” during a read operation of the memory cell array **210** and may operate as a “write circuit” during a write operation thereof.

[0102] The above-mentioned read-and-write circuit **230** is also referred to as a page buffer circuit including multiple page buffers PB, or a data register circuit. The read-and-write circuit **230** may include a data buffer in charge of a data processing function, and may further include a cache buffer in charge of a caching function, if necessary.

[0103] The multiple page buffers PB may be connected to the memory cell array **210** through multiple bit lines BL. During a read operation and a program verification operation, the multiple page buffers PB may continuously supply a sensing current to bit lines BL connected to memory cells, in order to sense the threshold voltage V_{th} of the memory cells, may sense a change in the amount of flowing current according to the program state of a corresponding memory cell through a sensing node, and may latch the same as sensing data.

[0104] The read-and-write circuit **230** may operate in response to page buffer control signals output from the control logic **240**.

[0105] During a read operation, the read-and-write circuit **230** senses data in a memory cell, temporarily stores the retrieved data, and outputs the data (DATA) to the input/output buffer of the memory device **110**. In an embodiment, the read-and-write circuit **230** may include a column selection circuit and the like in addition to the page buffers PB or page resistors.

[0106] The control logic **240** may be connected to the address decoder **220**, the read-and-write circuit **230**, the voltage generation circuit **250**, and the like. The control logic **240** may receive a command CMD and a control signal CTRL through the input/output buffer of the memory device **110**.

[0107] The control logic **240** may be configured to control overall operation of the memory device **110** in response to the control signal CTRL. The control logic **240** may output a control signal for adjusting the pre-charge potential level of sensing nodes of multiple page buffers PB.

[0108] The control logic **240** may control the read-and-write circuit **230** so as to perform a read operation of the memory cell array **210**. In response to a voltage generation circuit control signal output from the control logic **240**, the voltage generation circuit **250** may generate a read voltage V_{read} and a pass voltage V_{pass} , which are used during a read operation.

[0109] FIG. 3 is a diagram schematically illustrating respective memory blocks BLK of a memory device **110** according to an embodiment of the present disclosure.

[0110] Referring to FIG. 3, a memory block BLK included in a memory device **110** may include, for example, multiple pages PG and multiple strings STR disposed in intersecting directions.

[0111] The multiple pages PG correspond to multiple word lines WL, and the multiple string STR correspond to multiple bit lines BL.

[0112] The memory block BLK may have multiple word lines WL and multiple bit lines BL disposed so as to intersect with each other. For example, each of the multiple word lines WL may be disposed in a row direction, and each of the multiple bit lines BL may be disposed in a column direction. As another example, each of the multiple word lines WL may be disposed in the column direction, and each of the multiple bit lines BL may be disposed in the row direction.

[0113] Multiple word lines WL and multiple bit lines BL may intersect with each other, thereby defining multiple memory cells MC. Each memory cell MC may have a transistor TR disposed therein.

[0114] For example, the transistor TR disposed in each memory cell MC may include a drain, a source, a gate, and the like. The drain (or source) of the transistor TR may be directly connected to a corresponding bit line BL or connected thereto via another transistor TR. The source (or drain) of

the transistor TR may be directly connected to a source line (which may be ground) or connected thereto via another transistor TR. The gate of the transistor TR may include a floating gate (FG) surrounded by an insulator and a control gate (CG) to which a gate voltage is applied from a word line WL.

[0115] Each of the multiple memory blocks BLK1-BLKz may have a first selection line (also referred to as a source selection line or a drain selection line) additionally disposed outside a first outermost word line, which is closer to the read-and-write circuit **230** among two outermost word lines BL, and may have a second selection line (also referred to as a drain selection line or a source selection line) additionally disposed outside a second outermost word line, which is the other among the same.

[0116] If necessary, at least one dummy word line may be additionally disposed between the first outermost word line and the first selection line. In addition, at least one dummy word line may be additionally disposed between the second outermost word line and the second selection line.

[0117] When having a memory block structure as illustrated in FIG. **3**, a read operation and a program operation (write operation) may be performed page by page, and an erasure operation may be performed for each memory block.

[0118] FIG. **4** is a diagram illustrating the structure of word lines WL and bit lines BL of a memory device **110** according to an embodiment of the present disclosure.

[0119] Referring to FIG. **4**, the memory device **110** includes a core area in which memory cells MC are concentrated and an auxiliary area which corresponds to the other area than the core area, and which supports operations of the memory cell array **210**.

[0120] The core area may include pages PG and string STR. The core area has multiple word lines WL1-WL9 and multiple bit lines BL disposed to intersect with each other.

[0121] The multiple word lines WL1-WL9 may be connected to a row decoder **410**, and the multiple bit lines BL may be connected to a column decoder **420**. A data register **430**, which corresponds to a read-and-write circuit **230**, may exist between the multiple bit lines BL and the column decoder **420**.

[0122] The multiple word lines WL1-WL9 correspond to multiple pages PG.

[0123] For example, as illustrated in FIG. **4**, each of the multiple word lines WL1-WL9 may correspond to one page PG. Alternatively, when each of the multiple word lines WL1-WL9 has a large size, each of the multiple word lines WL1-WL9 may correspond to at least two (for example, two or four) pages PG. A page PG serves as the smallest unit in connection with conducting a program operation and a read operation, and all memory cells MC in the same page PG may perform simultaneous operations during a program operation and a read operation.

[0124] Among the multiple bit lines BL, odd-numbers bit lines BL and even-numbered bit lines BL may be distinguished and accordingly connected to the column decoder **420**.

[0125] In order to access a memory cell MC, the address goes through the input/output end and then enters the core area through the row decoder **410** and the column decoder **420**, and the target memory cell then can be designated. As used herein, designating a target memory cell refers to accessing one of memory cells MC at sites of intersection between word lines WL1-WL9 connected to the row decoder **410** and bit lines BL connected to the column decoder **420**, in order to program data therein or to read programmed data therefrom.

[0126] Pages PG in a first direction (for example, X-axis direction) are grouped by a commonly used line referred to as a word line WL, and strings STR in a second direction (for example, Y-axis direction) are grouped (connected) by a common line referred to as a bit line BL. As used herein, being commonly grouped means that they are structurally connected by the same material, and the same voltage is simultaneously applied thereto during voltage application. Obviously, the voltage applied to a memory cell MC in the intermediate or last position among memory cells MC connected in series may slightly differ from the voltage applied to the memory cell MC in the first position and the voltage applied to the memory cell MC in the last position, due to the voltage drop

occurring in the memory cell MC positioned in front thereof.

[0127] All data processed by the memory device **110** is programmed and read via the data register **430**, which thus plays an essential role. If data processing by the data register **430** slows down, all other areas need to wait until the data register **430** finishes the data processing. In addition, performance degradation of the data register **430** may be followed by overall performance degradation of the memory device **110**.

[0128] Referring to the example in FIG. **4**, multiple transistors TR**1**-TR**9** may exist in one string STR while being connected to multiple word lines WL**1**-WL**9**. The areas in which the multiple transistors TR**1**-TR**9** exist correspond to memory cells MC. The multiple transistors TR**1**-TR**9** are transistors including control gates CG and floating gates FG, as described above.

[0129] The multiple word lines WL**1**-WL**9** include two outermost word lines WL**1** and WL**9**. A first selection line DSL may be additionally disposed outside the first outermost word line WL**1**, which is closer to the data register **430** in terms of the signal path among the two outermost word lines WL**1** and WL**9**, and a second selection line SSL may be additionally disposed outside the second outermost word line WL**9** which is the other thereof.

[0130] The first selection transistor D-TR, which is controlled to turn on/off by the first selection line DSL, has a gate electrode connected to the first selection line DSL but includes no floating gate FG. The second selection transistor S-TR, which is controlled to turn on/off by the second selection line SSL, has a gate electrode connected to the second selection line SSL but includes no floating gate FG.

[0131] The first selection transistor D-TR plays the role of a switch that turns on or off the connection between the corresponding string STR and the data register **430**. The second selection transistor S-TR plays the role of a switch that turns on or off the connection between the corresponding string STR and the source line SL. That is, the first selection transistor D-TR and the second selection transistor S-TR are positioned on both ends of the corresponding string STR and play the role of gatekeepers that connect and disconnect signals.

[0132] During a program operation, the memory system **100** needs to fill the target memory cell MC of the bit line BL, which is to be programmed, with electrons. Accordingly, the memory system **100** applies a turn-on voltage V_{cc} to the gate electrode of the first selection transistor D-TR, thereby turning on the first selection transistor D-TR, and applies a turn-off voltage (for example, OV) to the gate electrode of the second selection transistor S-TR, thereby turning off the second selection transistor S-TR.

[0133] During a read operation or a verification operation, the memory system **100** turns on both the first selection transistor D-TR and the second selection transistor S-TR. Accordingly, a current may flow through the corresponding string STR and drain to a source line SL corresponding to the ground, thereby making it possible to measure the voltage level of the bit line BL. However, during a read operation, there may be a time difference in the on-off timing between the first selection transistor D-TR and the second selection transistor S-TR.

[0134] During an erasure operation, the memory system **100** may supply a voltage (for example, +20V) to the substrate through the source line SL. During the erasure operation, the memory system **100** floats both the first selection transistor D-TR and the second selection transistor S-TR, thereby generating an infinite resistance. The resulting structure removes the roles of the first selection transistor D-TR and the second selection transistor S-TR, and enables electrons to operate by means of the potential difference only between the floating gate FG and the substrate.

[0135] FIG. **5** is a timing diagram regarding operations of a memory system **100** according to an embodiment of the present disclosure.

[0136] The memory controller **120** included in the memory system **100** may perform garbage collection with regard to the memory device **100** on the basis of a first amount of time TIME_1 and a second amount of time TIME_2. If it is determined that garbage collection needs to be performed, the memory controller **120** may start a preparatory operation (for example, stopping an ongoing

read/write/erasure operation) needed to perform the garbage collection. When the preparatory operation starts, a garbage collection operation may be triggered.

[0137] The first amount of time **TIME_1** refers to a period of time between triggering of first garbage collection **GC_1** and triggering of second garbage collection **GC_2**. That is, **TIME_1** corresponds to a period during which garbage collection is performed; **TIME_1** may be repeated at a certain frequency.

[0138] During the first amount of time **TIME_1**, the memory controller **120** may perform triggered first garbage collection **GC_1**. In addition, during **TIME_1**, the memory controller **120** may read user data requested by the host from the memory device **110** or may write the same in the memory device **110**.

[0139] The second amount of time **TIME_2** refers to an amount of time taken to perform second garbage collection **GC_2**. Once the second garbage collection **GC_2** is triggered, the memory controller **120** performs the second garbage collection **GC_2** during **TIME_2**.

[0140] The memory controller **120** may perform second garbage collection **GC_2** the moment the second garbage collection **GC_2** is triggered. Alternatively, the memory controller **120** may perform second garbage collection **GC_2** a specific amount of time after the second garbage collection **GC_2** is triggered.

[0141] The longer **TIME_1** becomes, the less frequently garbage collection is performed under the assumption of **TIME_2** being fixed. This means that the ratio of garbage collection to all operations performed by the memory system **100** decreases. On the other hand, the longer **TIME_2** becomes, the longer garbage collection is performed under the assumption of **TIME_1** being fixed. This means that the ratio of garbage collection to all operations performed by the memory system **100** increases. Therefore, the memory system **100** may determine the ratio of garbage collection to all operations performed, on the basis of **TIME_1** and **TIME_2**.

[0142] The memory system **100** may determine the above-mentioned **TIME_1** and **TIME_2** in various methods. Hereinafter, a criterion by which the memory system **100** determines **TIME_1** and **TIME_2** is described with reference to FIG. 6.

[0143] FIG. 6 is a diagram illustrating a criterion used by the memory system **100** according to an embodiment of the present disclosure to determine **TIME_1** and **TIME_2**.

[0144] The memory controller **120** of the memory system **100** may determine **TIME_1** and **TIME_2** such that the ratio of **TIME_1** to **TIME_2** becomes a target ratio value (for example, 3:1 or 5:1).

[0145] For example, the memory controller **120** may determine, in FIG. 6, the ratio of **TIME_1** to **TIME_2** to be 5:1.

[0146] The memory controller **120** may determine **TIME_2** to be equal to or longer than a minimum garbage collection operation time.

[0147] For example, the minimum garbage collection operation time is 10 ms in FIG. 6.

[0148] In FIG. 6, pairs of **TIME_1** and **TIME_2**, the ratio of which is 5:1, may include (25,5), (50, 10), (75, 15), (100, 20), and (125, 25).

[0149] The memory controller **120** may select, from the above-mentioned pairs, a pair satisfying the condition that the minimum garbage collection operation time is 10 ms or longer. In FIG. 6, the memory controller **120** may select (50, 10) and may control **TIME_1** and **TIME_2** to be 50 ms and 10 ms, respectively.

[0150] The reason the memory controller **120** of the memory system **100** determines **TIME_1** and **TIME_2** such that the above-mentioned criterion is satisfied, in an embodiment of the present disclosure, is as follows:

[0151] As described with reference to FIG. 5, the longer the first amount of time **TIME_1**, the smaller the ratio of garbage collection performed among to all operations. The longer the second amount of time **TIME_2**, the greater the ratio of garbage collection performed among all operations.

[0152] Therefore, the memory controller **120** of the memory system **100** may determine a target ratio of TIME_1 to TIME_2 such that an appropriate ratio of garbage collection, relative to all operations, is performed. This may enable the memory controller **120** to perform efficient garbage collection.

[0153] A longer TIME_2 interrupts other operations (for example, reading/writing user data) for a longer amount of time. Therefore, while garbage collection is performed, a read operation or a write operation may be delayed. Consequently, if TIME_2 becomes too long, the memory system **100** may fail to satisfy the performance criterion required by the host.

[0154] On the other hand, a shorter TIME_2 may mean that a smaller number of free memory blocks are secured each time garbage collection is performed, and thus garbage collection is more frequently triggered. Frequent garbage collection requires overhead that can adversely affect the performance of the memory system **100**.

[0155] Therefore, the memory controller **120** of the memory system **100** may select an appropriate value of TIME_2, which is equal to or longer than the minimum garbage collection operation time, so as to reduce overhead resulting from garbage collection and to satisfy the performance criterion (i.e., read/write latency) desired by the host. This may enable the memory controller **120** to perform efficient garbage collection.

[0156] The memory controller **120** may determine TIME_1 and TIME_2, which satisfy the above-mentioned criterion, in various methods. Hereinafter, a specific method for determining TIME_1 and TIME_2 by the memory controller **120** according to an embodiment is described with reference to the drawings.

[0157] A method for determining TIME_1 by the memory controller **120** is described first.

[0158] FIG. 7 is a diagram illustrating an example of determining TIME_1 in a memory system **100** according to an embodiment of the present disclosure.

[0159] For example, the memory controller **120** of the memory system **100** may determine TIME_1 on the basis of a time at which the total amount of the size of user data written in the memory device **110**, since first garbage collection GC_1 is triggered, becomes equal to or greater than a threshold.

[0160] Referring to FIG. 7, after first garbage collection GC_1 is triggered, the host requests that 50 KB of user data be read from the memory system **100** ({circle around (1)}). Thereafter, the host requests that 100 KB of user data be written in the memory system **100** ({circle around (2)}), and requests 50 KB of user data be written therein ({circle around (3)}). Thereafter, the host requests that 50 KB of user data be read from the memory system **100** ({circle around (4)}), and requests that 150 KB of user data be written in the memory system **100** ({circle around (5)}).

[0161] The memory controller **120** may trigger second garbage collection GC_2 when the total amount of the size of user data written in the memory device **110**, since first garbage collection GC_1 is triggered, becomes equal to or greater than a threshold. It is assumed in FIG. 7 that the threshold is 300 KB.

[0162] In FIG. 7, the host requests the memory system **100** to write 150 KB of user data, and the memory system **100** writes, in response thereto, 150 KB of user data in the memory device **110**. The total amount of the size of user data written in the memory device **110**, since first garbage collection GC_1 is triggered, becomes equal to or greater than a threshold of 100 KB+50 KB+150 KB=300 KB.

[0163] Then, the memory controller **120** of the memory system **100** may accordingly trigger second garbage collection GC_2. The first amount of time TIME_1 is determined as a period of time between triggering of first garbage collection GC_1 and triggering of second garbage collection GC_2.

[0164] The reason the memory controller **120** determines TIME_1 on the basis of the time at which the total amount of the size of user data written in the memory device **110** becomes equal to or greater than the threshold in FIG. 7 is because the user data writing operation has the largest

influence on determining whether or not to perform garbage collection.

[0165] Specifically, if the size of invalid data increases while the size of valid data (i.e., user data) is increasing in the memory device **110** due to writing operations, the memory controller **120** may perform garbage collection.

[0166] On the other hand, other operations (for example, reading user data and erasing memory blocks) do not affect the total size of data in the memory device **110** since the size of valid data does not increase or can even decrease although the size of invalid data can increase. Therefore, other operations (for example, reading user data and erasing memory blocks) have no substantial influence on determining whether or not to perform garbage collection. In addition, if the memory controller **120** considers other operations to determine TIME_1, many factors need to be taken into account to determine TIME_1, thereby increasing the overhead for determining TIME_1.

[0167] Accordingly, in the above-described embodiment, the memory controller **120** may determine TIME_1 on the basis of the time at which the total amount of the size of user data written in the memory device **110**, since first garbage collection GC_1 is triggered, becomes equal to or greater than a threshold.

[0168] An example of determining TIME_1 by the memory controller **120** has been described above.

[0169] Hereinafter, an example of determining the second amount of time TIME_2 to be equal to or longer than the minimum garbage collection operation time by the memory controller **120** is described.

[0170] FIG. 8 is a diagram illustrating an example of determining TIME_2 in a memory system **100** according to an embodiment of the present disclosure.

[0171] The memory controller **120** of the memory system **100** may determine TIME_2 on the basis of a performance drop value X. The performance drop value X may have a range of 0 to 100. The performance drop value X is the ratio (%) of garbage collection to all operations performed by the memory system **100**. This means that the memory system **100** uses X % of all operations performed by the memory system **100** to perform garbage collection.

[0172] In an embodiment of the present disclosure, a method for determining the second amount of time TIME_2, during which second garbage GC_2 collection is performed, in order to determine the optimal time to perform garbage collection, on the basis of the performance drop value X, is described.

[0173] Hereinafter, a method for determining TIME_2 on the basis of the performance drop value X is described.

[0174] In embodiments of the present disclosure, the entire performance or resources of the memory system **100** may be defined as the sum of the performance or resources for garbage collection (GC_PERFORM) and the performance or resources used to process user data (USER_PERFORM). USER_PERFORM includes, for example, read and write processing.

[0175] A performance drop value of X may be defined by Equation 1 below:

[00001] $X: (100 - X) = GC_PERFORM: USER_PERFORM$ [Equation1]

[0176] What is frequently performed when garbage collection is performed is an operation of writing data in the memory device **110**, that is, operation of writing valid data stored in a memory block of the memory device **110** in another memory block of the memory device **110**. Therefore, the performance used for garbage collection (GC_PERFORM) is proportional to a first data size DATA_SIZE_1, which is the size of data written in the memory device **110** when second garbage collection GC_2 is performed.

[0177] In addition, an operation of writing user data during an operation of processing user data has a large influence on performing garbage collection, as described with reference to FIG. 7.

Accordingly, the USER_PERFORM is proportional to a second data size DATA_SIZE_2, which is the size of user data written in the memory device **110** after first garbage collection GC_1 within

the first amount of time TIME_1.

[0178] Therefore, the above-mentioned Equation 1 may also be expressed by Equation 2 below:

[00002] $X: (100 - X) = \text{DATA_SIZE_1} : \text{DATA_SIZE_2}$ [Equation2]

[0179] In Equation 2 above, the first data size DATA_SIZE_1 may be determined by determining the performance drop value X and the second data size DATA_SIZE_2.

[0180] FIG. 9 is a diagram illustrating an example of determining DATA_SIZE_1 in order to determine the TIME_2 in a memory system 100 according to an embodiment of the present disclosure.

[0181] It will be assumed in FIG. 9 that the performance drop value X is 30, and the second data size DATA_SIZE_2 is 100 KB+100 KB+150 KB=350 KB.

[0182] The first data size DATA_SIZE_1 may then be determined as follows:

[00003]
$$30: 70 = \text{DATA_SIZE_1} : 350\text{KB}$$
$$\text{DATA_SIZE_1} = ((350\text{KB} * 30) / 70) = 150\text{KB}$$

[0183] After the first data size DATA_SIZE_1 is determined in this manner, TIME_2 may be determined as follows:

[0184] For example, TIME_2 may be determined on the basis of a value obtained by dividing the first data size DATA_SIZE_1 by the number of partial programs (NOP) representing a number of unit pieces of data that can be programmed in the memory device 110 per a set amount of time (for example, 100 ms). A unit piece of data may have a size equal to or smaller than the page size (for example, 4 KB or 8 KB).

[0185] It will be assumed for example that the unit piece of data is 1 KB, and NOP is 100. This means that 100 KB of data can be written in the memory device 110 per 100 ms. Accordingly, if the first data size DATA_SIZE_1 is 150 KB, the second amount of time TIME_2 may be determined as $(150 \text{ KB} / (100 * (1 \text{ KB}))) * 100 = 150 \text{ (ms)}$.

[0186] It has been described in the above embodiment that the user data writing operation, among user data processing operations, has a large influence on garbage collection. Accordingly, the performance used to process user data (USER_PERFORM) has been defined as the performance used to write user data having the second data size DATA_SIZE_2 described above.

[0187] However, if the memory system 100 performs the operation of reading user data from the memory device 110 more frequently than the operation of writing user data in the memory device 110, most resources used to process user data may be assigned to the operation of reading user data from the memory device 110. In this case, the performance used to process user data (USER_PERFORM) is preferably defined as the performance used to read user data, instead of the performance used to write user data having the second data size DATA_SIZE_2.

[0188] Therefore, the performance used to process user data (USER_PERFORM) may also be defined as a read time READ_TIME, which is the time spent to perform an operation of reading user data after first garbage collection GC_1 within the first amount of time TIME_1.

[0189] In this case, with regard to a performance drop value X, the second amount of time TIME_2 may be determined by Equation 3 below:

[00004] $X: (100 - X) = \text{TIME_2} : \text{READ_TIME}$ [Equation3]

[0190] FIG. 10 is a diagram illustrating another example of determining TIME_2 in a memory system 100 according to an embodiment of the present disclosure.

[0191] It will be assumed in FIG. 10 that the performance drop value X is 30, and that the time spent to perform the operation of reading 200 KB of user data is 70 ms within the first amount of time TIME_1.

[0192] In this case, the second amount of time TIME_2 may be determined by Equation 3 given above in the following manner:

30: (100 - 30) = TIME_2: 70ms
[00005]

TIME_2 = 30ms

[0193] To summarize the description of FIGS. 5 to 10, the memory system 100 may determine TIME_1 and TIME_2 so as to satisfy a criterion (for example, performance drop value, the ratio between TIME_1 and TIME_2, or minimum garbage collection operation time), and may perform garbage collection on the basis thereof.

[0194] This makes it unnecessary to tune parameters necessary for the garbage collection operation for each device having the memory system 100 implemented therein. Accordingly, the overhead occurring in the process of tuning parameters necessary for the garbage collection operation is reduced.

[0195] In addition, even if the criterion is changed by varying external environments (for example, power supply and temperature), the memory system 100 can change TIME_1 and TIME_2 such that the garbage collection operation can be optimized according to the changed criterion. This enables the memory system 100 to flexibly handle the varying external environments.

[0196] FIG. 11 is a diagram illustrating a method for operating the memory controller 120 according to an embodiment of the present disclosure.

[0197] The method for operating the memory controller 120 may include a step of determining a first amount of time TIME_1, which is the period of time between triggering of first garbage collection GC_1 and triggering of second garbage collection GC_2 (S1110).

[0198] In addition, the method for operating the memory controller 120 may include a step of determining a second amount of time TIME_2, which is the time necessary to perform the second garbage collection GC_2 (S1120).

[0199] In addition, the method for operating the memory controller 120 may include a step of performing garbage collection with regard to the memory device 110 on the basis of TIME_1 and TIME_2 (S1130).

[0200] The ratio TIME_1 to TIME_2 may be determined as a target ratio value, and TIME_2 may be determined to be equal to or longer than a minimum garbage collection operation time.

[0201] FIG. 12 is a flowchart illustrating a method for determining the second amount of time TIME_2 in the memory system 100 according to an embodiment of the present disclosure.

[0202] The method for determining the second amount of time TIME_2 may include a step of determining a performance drop value X (S1210).

[0203] In addition, the method for determining TIME_2 may include a step of determining a first data size DATA_SIZE_1, which is the size of data written in the memory device 110 when performing second garbage collection GC_2, on the basis of the performance drop value X determined in step S1210 (S1220).

[0204] The first data size DATA_SIZE_1 may be determined on the basis of the performance drop value X and a second data size DATA_SIZE_2, which is the size of user data written in the memory device 110 after garbage collection is triggered.

[0205] TIME_2 may then be determined on the basis of the above-mentioned performance drop value, the first data size DATA_SIZE_1, and the second data size DATA_SIZE_2 (S1230).

[0206] The above-described operations of the memory controller 120 may be controlled by the control circuit 123, and may be performed in such a manner that the processor 124 executes (drives) firmware to perform such operations.

[0207] FIG. 13 is a diagram illustrating a configuration of a computing system 1300 according to an embodiment of the present disclosure.

[0208] Referring to FIG. 13, the computing system 1300 may include: a memory system 100 electrically connected to a system bus 1360; a CPU 1310 configured to control overall operation of the computing system 1300; a RAM 1320 configured to store data and information related to operations of the computing system 1300; a user interface/user experience (UI/UX) module 1330

configured to provide the user with a user environment; a communication module **1340** configured to communicate with an external device in a wired/and/or wireless manner; a power management module **1350** configured to manage power used by the computing system **1300**; and the like.

[0209] The computing system **1300** may be a personal computer (PC) or may include a mobile terminal (for example, a smartphone or a tablet) or various kinds of other electronic devices.

[0210] The computing system **1300** may further include a battery for supplying a dynamic voltage, an application chipset, a graphic-related module, a camera image processor (CIS), and a DRAM. It is obvious to a person skilled in the art that the computing system **1300** may further include other components.

[0211] The memory system **100** may include not only a device configured to store data in a magnetic disk, such as a hard disk drive (HDD), but also a device configured to store data in a nonvolatile memory, such as a solid state drive (SSD), a universal flash storage (UFS) device, and an embedded MMC (eMMC) device. The nonvolatile memory may include a read only memory (ROM), a programmable ROM (PROM), an electrically programmable ROM (EPROM), an electrically erasable and programmable ROM (EEPROM), a flash memory, a phase-change RAM (PRAM), a magnetic RAM (MRAM), a resistive RAM (RRAM), and a ferroelectric RAM (FRAM). Furthermore, the memory system **100** may be implemented as any of various storage devices mounted inside any of various electronic devices.

[0212] Although the present invention has been illustrated and described in connection with various embodiments, those skilled in the art will appreciate that various modifications and changes may be made without departing from the scope and spirit of the present invention. Thus, the present invention is not limited by or to any of the disclosed embodiments. Rather, the present invention encompasses all modifications and variations that fall within the scope of the claims including their equivalents.

Claims

1. A memory system comprising: a memory device; and a memory controller configured to control the memory device, wherein the memory controller is further configured to: perform first garbage collection and second garbage collection with regard to the memory device on the basis of a first amount of time and a second amount of time determined by the first garbage collection and the second garbage collection, wherein the first amount of time being a period of time between triggering time point of first garbage collection and triggering time point of second garbage collection, and the second amount of time being an amount of time necessary to perform the second garbage collection; determine a ratio of the first amount of time to the second amount of time to be a target ratio value of garbage collection; and determine the second amount of time to be equal to or longer than a minimum garbage collection operation time.
