

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication
Kind Code
Publication Date
Inventor(s)

20250280419
A1
September 04, 2025
YANG; Hyo Sun et al.

METHOD AND APPARATUS FOR SUPPORTING A PLURALITY OF CONFIGURED GRANTS IN WIRELESS COMMUNICATION SYSTEM

Abstract

The present disclosure can provide a method in which a terminal performs transmission in a wireless communication system. The method for performing transmission can comprise the steps in which: a terminal receives a plurality of pre-configured resources; the device confirms as to whether the plurality of pre-configured resources collide; the terminal selects any one pre-configured resource among a plurality of collided pre-configured resources; and transmission for the selected preconfigured resource is performed.

Inventors: YANG; Hyo Sun (Seoul, KR), KWON; Ki Bum (Seoul, KR)
Applicant: Innovative Technology Lab Co., Ltd. (Seoul, KR)
Family ID: 72609077
Appl. No.: 19/211822
Filed: May 19, 2025

Foreign Application Priority Data

KR 10-2019-0036365 Mar. 28, 2019

Related U.S. Application Data

parent US continuation 17487253 20210928 parent-grant-document US 12342346 child US 19211822
parent WO continuation PCT/KR2020/004199 20200327 PENDING child US 17487253

Publication Classification

Int. Cl.: H04W72/23 (20230101); H04L1/1812 (20230101); H04L5/00 (20060101)
U.S. Cl.:
CPC H04W72/23 (20230101); H04L1/1812 (20130101); H04L5/0098 (20130101);

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation of U.S. application Ser. No. 17/487,253, filed on Sep. 28, 2021, which is a continuation of International patent application No. PCT/KR2020/004199, filed on Mar. 27, 2020, which claims priority from and the benefit of Korean Patent Application No. 10-2019-0036365, filed on Mar. 28, 2019, each of which is hereby incorporated by reference in its entirety.

BACKGROUND

1. Field

[0002] The present disclosure relates to a method and apparatus for supporting a plurality of configured grants in a wireless communication system and, more particularly, to a method and apparatus for configuring, by a user equipment (UE) supporting Ultra Reliable and Low Latency Communications (URLLC) and Industrial Internet of Things (IIoT), a plurality of configured grants.

2. Discussion of the Background

[0003] International Mobile Telecommunication (IMT) framework and standard are being developed in the International Telecommunication Union (ITU). Also, in the recent times, discussion for 5-th generation (5G) communication is ongoing through a program called “IMT for 2020 and beyond.”

[0004] To meet the requirements requested by “IMT for 2020 and beyond,” discussion is being made to support various numerologies about a time-frequency resource unit standard by considering various scenarios, service requirements, and potential system compatibility in a 3-rd Generation Partnership Project (3GPP) new radio (NR) system.

SUMMARY

[0005] The present disclosure may provide a method and apparatus for supporting a plurality of configured grants.

[0006] The present disclosure may provide a method and apparatus for configuring, by a user equipment (UE) supporting Ultra Reliable and Low Latency Communications (URLLC) and Industrial Internet of Things (IIoT), a plurality of configured grants.

[0007] The present disclosure may provide a method and apparatus for selecting, by a UE, a single configured grant and transmitting data if a plurality of configured grants collides.

[0008] The present disclosure may provide a method and apparatus for retransmitting, by a UE, data of which transmission is omitted through an omitted configured grant if a plurality of configured grants collides.

[0009] According to an example of the present disclosure, there may be provided a method of performing, by a user equipment (UE), transmission in a wireless communication system. Here, the method of performing transmission may include receiving, by the UE, a plurality of configured grants, wherein the receiving includes receiving a configured grant for at least one service configured in a single bandwidth part (BWP), the configured grant is configured for each service, and at least one configured grant is configured for the service; verifying, by the UE, whether a collision occurs between the plurality of configured grants, wherein the verifying includes verifying whether transmission points in times for transmitting traffic overlap between the services; selecting, by the UE, a single configured grant from among the colliding plurality of configured grants, wherein the selecting of the single configured grant includes a process of verifying priority for the service from a radio resource control (RRC) message received from the base station and a process of selecting a configured grant based on the verified priority, and further includes a process of selecting an initially configured grant based on time order when transmission points in times of traffic for the same service overlap; and transmitting traffic for a corresponding service using the selected configured grant.

[0010] Also, according to an example of the present disclosure, in the receiving of the configured grant, a first BWP supports services A, B, and C, the configured grant is configured for each of the services A, B, and C, and at least one configured grant is configured for each of the services A, B, and C, a second BWP supports services D and E, the configured grant is configured for each of the services D and E, and at least one configured grant is configured for each of the services D and E, and the receiving of the configured grant includes a process of activating, by the UE, a BWP indicated by a BWP indicator included in a Physical Downlink Control Channel (PDCCH) received from the base station and inactivating a BWP not indicated between the first BWP and the second BWP.

[0011] Also, according to an example of the present disclosure, the services A, B, and C and the services D and E may indicate the same service.

[0012] Also, according to an example of the present disclosure, the receiving of the configured grant may include verifying a transmission point in time of traffic for each of the services A, B, and C using the configured grant for each of the services A, B, and C of the activated first BWP; and verifying whether transmission points in times of traffic overlap among the services A, B, and C.

[0013] Also, according to an example of the present disclosure, the method may further include a process of receiving an uplink grant from the base station using a configured scheduling radio network temporary identifier (CS-RNTI) for retransmission of a configured grant configured for the UE, and a process of transmitting traffic for a service corresponding to a dropped configured grant using the received uplink grant.

[0014] Here, according to an example of the present disclosure, the process of transmitting the traffic for the service may include a process of receiving allocation of a retransmission grant addressed to the CS-RNTI, and a process of verifying retransmission of traffic for a corresponding service by verifying a Hybrid ARQ Automatic Repeat and Repeat (HARQ) process identifier (ID) of the retransmission grant.

[0015] Also, according to an example of the present disclosure, the method may further include a process of receiving an uplink grant from the base station using a C-RNTI and a process of transmitting traffic for a service corresponding to a dropped configured grant using the received uplink grant.

[0016] Features briefly described above in relation to the present disclosure are merely example aspects of the following detailed description and do not limit the scope of the present disclosure.

[0017] According to the present disclosure, there may be provided a method and apparatus for supporting a plurality of configured grants.

[0018] According to the present disclosure, there may be provided a method and apparatus for configuring, by a user equipment (UE) supporting Ultra Reliable and Low Latency Communications (URLLC) and Industrial Internet of Things (IIoT), a plurality of configured grants.

[0019] According to the present disclosure, there may be provided a method and apparatus for selecting, by a UE, a single configured grant and transmitting data if a plurality of configured grants collides.

[0020] According to the present disclosure, there may be provided a method and apparatus for retransmitting, by a UE, data of which transmission is omitted through an omitted configured grant if a plurality of configured grants collides.

[0021] Effects achievable from the present disclosure are not limited to the aforementioned effects and still other effects not described herein may be clearly understood by one of ordinary skill in the art to which the present disclosure pertains from the following description.

Description

BRIEF DESCRIPTION OF THE DRAWINGS

[0022] FIG. 1 illustrates a wireless communication system according to the present disclosure.

[0023] FIG. 2 illustrates a bandwidth part (WP) configuration according to the present disclosure.

[0024] FIG. 3 illustrates a scenario in which a collision occurs between a plurality of configured grants according to the present disclosure.

[0025] FIG. 4 illustrates an uplink transmission operation of a user equipment (UE) according to the present disclosure.

[0026] FIG. 5 illustrates an uplink transmission operation of a UE according to the present disclosure.

[0027] FIG. 6 illustrates an operation of a UE according to the present disclosure.

[0028] FIG. 7 illustrates an operation of a UE according to the present disclosure.

[0029] FIG. 8 illustrates an operation of a UE according to the present disclosure.

[0030] FIG. 9 is a flowchart illustrating an operation of a UE according to the present disclosure.

[0031] FIG. 10 is a flowchart illustrating an operation of a UE according to the present disclosure.

[0032] FIG. 11 is a flowchart illustrating an operation of a UE according to the present disclosure.

[0033] FIG. 12 is a diagram illustrating a configuration of a base station device and a terminal device according to the present disclosure.

DETAILED DESCRIPTION

[0034] According to an example of the present disclosure, there may be provided a method of performing, by a user equipment (UE), transmission in a wireless communication system. Here, the method of performing transmission may include receiving, by the UE, a plurality of configured grants, wherein the receiving includes receiving a configured grant for at least one service configured in a single bandwidth part (BWP), the configured grant is configured for each service, and at least one configured grant is configured for the service; verifying, by the UE, whether a collision occurs between the plurality of configured grants, wherein the verifying includes verifying whether transmission points in times for transmitting traffic overlap between the services; selecting, by the UE, a single configured grant from among the colliding plurality of configured grants, wherein the selecting of the single configured grant includes a process of verifying priority for the service from a radio resource control (RRC) message received from the base station and a process of selecting a configured grant based on the verified priority, and further includes a process of selecting an initially configured grant based on time order when transmission points in times of traffic for the same service overlap; and transmitting traffic for a corresponding service using the selected configured grant.

[0035] Various examples of the present disclosure will be described more fully hereinafter with reference to the accompanying drawings such that one of ordinary skill in the art to which the present disclosure pertains may easily implement the examples. However, the present disclosure may be implemented in various forms and is not limited to the examples described herein.

[0036] In describing the examples, detailed description on known configurations or functions may be omitted for clarity and conciseness. Throughout

the drawings and the detailed description, unless otherwise described, the same drawing reference numerals are understood to refer to the same elements, features, and structures.

[0037] In the present disclosure, it will be understood that when an element is referred to as being “connected to,” “coupled to,” or “accessed to” another element, it can be directly connected, coupled, or accessed to the other element or intervening elements may be present. Also, it will be further understood that when an element is described to “comprise/include” or “have” another element, it specifies the presence of still another element, but does not preclude the presence of another element unless otherwise described.

[0038] In the present disclosure, the terms, such as first, second, and the like, may be used herein to describe elements in the description herein. The terms are used to distinguish one element from another element. Thus, the terms do not limit the element, an arrangement order, a sequence or the like. Therefore, a first element in an example may be referred to as a second element in another example. Likewise, a second element in an example may be referred to as a first element in another example.

[0039] In present disclosure, distinguishing elements are merely provided to clearly explain the respective features and do not represent that the elements are necessarily separate from each other. That is, a plurality of elements may be integrated into a single hardware or software unit. Also, a single element may be distributed to a plurality of hardware or software units. Therefore, unless particularly described, the integrated or distributed example is also included in the scope of the disclosure.

[0040] In the present disclosure, elements described in various examples may not be necessarily essential and may be partially selectable. Therefore, an example including a partial set of elements described in an example is also included in the scope of the disclosure. Also, an example that additionally includes another element to elements described in various examples is also included in the scope of the disclosure.

[0041] Further, the description described herein is related to a wireless communication network, and an operation performed in the wireless communication network may be performed in a process of controlling a network and transmitting data in a system that controls the wireless communication network (e.g., a base station), or may be performed in a process of transmitting or receiving a signal in a user equipment connected to the wireless communication network.

[0042] It is apparent that various operations performed for communication with a terminal in a network including a base station and a plurality of network nodes may be performed by the base station or by other network nodes in addition to the base station. Here, the term ‘base station (BS)’ may be interchangeably used with other terms, for example, a fixed station, a Node B, eNodeB (eNB), and an access point (AP). Also, the term ‘terminal’ may be interchangeably used with other terms, for example, user equipment (UE), a mobile station (MS), a mobile subscriber station (MSS), a subscriber station (SS), and a non-AP station (non-AP STA).

[0043] In the present disclosure, transmitting or receiving a channel includes a meaning of transmitting or receiving information or a signal through the corresponding channel. For example, transmitting a control channel indicates transmitting control information or a signal through the control channel. Likewise, transmitting a data channel indicates transmitting data information or a signal through the data channel.

[0044] In the following description, although the term “new radio (NR) system” is used to distinguish a system according to various examples of the present disclosure from the existing system, the scope of the present disclosure is not limited thereto.

[0045] For example, a new radio (NR) system supports various subcarrier spacings (SCSs) by considering various scenarios, service requirements, potential system compatibility, and the like. Also, to overcome a poor channel environment, such as high pathloss, phase-noise, and frequency offset, occurring on a high carrier frequency, the NR system may support transmission of a physical signal/channel through a plurality of beams. Through this, the NR system may support applications, for example, enhanced Mobile Broadband (eMBB), massive Machine Type Communications (mMTC)/ultra Machine Type Communications (uMTC), and Ultra Reliable and Low Latency Communications (URLLC). Here, the term “NR system” used herein is used as an example of a wireless communication system, and the term “NR system” itself is not limited to the aforementioned features.

[0046] Also, for example, 5-th generation (5G) mobile communication technology may be defined. Here, 5G mobile communication technology may be defined by including the existing Long Term Evolution-Advanced (LTE-A) system as well as the aforementioned NR system. That is, 5G mobile communication technology may operate by considering backward compatibility with a previous system as well as a newly defined NR system.

[0047] For example, a sidelink field of 5G may include all of sidelink technology in an LTE system and sidelink technology in an NR system. Here, the sidelink field may be essential to enhance a performance and to integrate various services through an ultra high reliability and an ultra low latency.

[0048] FIG. 1 is a diagram illustrating a wireless communication system to which the present disclosure is applied.

[0049] The network structure illustrated in FIG. 1 may be the network structure of NG-RAN (Next Generation Radio Access Network) or Evolved-Universal Mobile Telecommunications System (E-UMTS). NG-RAN or E-UMTS may include the long term evolution (LTE) system, the LTE-A system, or the like, or may include the 5G mobile communication network, new radio (NR), or the like.

[0050] Referring to FIG. 1, in a wireless communication system 10, a base station (BS) 11 and a user equipment (UE) 12 may wirelessly perform transmission and reception of data. Also, the wireless communication system 10 may support device-to-device (D2D) communication between UEs. Also, for example, the wireless communication system 10 may support Vehicle-to-everything (V2X) communication. The following may include all of the concept of a terminal device used by a general user and a terminal device mounted to a vehicle, such as, for example, a smartphone for the aforementioned UE.

[0051] Also, for example, the BS 11 in the wireless communication system 10 may provide a communication service to a UE placed in the coverage of the BS 11 via a predetermined frequency band. The coverage within which a BS provides a service is also referred to as a site. The site may include various areas 15a, 15b, and 15c, which may be referred to as sectors. The sectors included in the site may be identified by different identifiers. Each sector 15a, 15b, and 15c may be construed as a part of the area that the BS 11 covers.

[0052] Also, for example, the BS 11 may generally refer to a station that communicates with the UE 12, and may be referred to as an evolved-NodeB (eNodeB), gNodeB, ng-eNB, a base transceiver system (BTS), an access point, a femtoNodeB, a home eNodeB (HeNodeB), a relay, a remote radio head (RRH), DU (Distributed Unit) or the like.

[0053] The UE 12 may be a stationary or mobile entity, and may be referred to as a mobile station (MS), a mobile terminal (MT), a user terminal (UT), a subscriber station (SS), a wireless device, a personal digital assistant (PDA), a wireless modem, a handheld device, or the like.

[0054] Also, the BS 11 may be referred to as “megacell,” “macrocell,” “microcell,” “picocell,” “femtocell,” or the like based on the size of coverage provided by the corresponding BS. A cell may be used as a term for indicating a frequency band that a BS provides, the coverage of a BS, or a BS.

[0055] Hereinafter, a downlink (DL) indicates communication or a communication path from the BS 11 to the UE 12, and an uplink (UL) indicates communication or a communication path from the UE 12 to the BS 11. In the downlink, a transmitter may be a part of the BS 11, and a receiver may be a part of the UE 12. In the uplink, a transmitter may be a part of the UE 12, and a receiver may be a part of the BS 11.

[0056] A multiple access scheme applied to the wireless communication system 10 is not limited to a specific scheme. For example, the wireless communication system may utilize various multiple access schemes, such as code division multiple access (CDMA), time division multiple access (TDMA), frequency division multiple access (FDMA), orthogonal frequency division multiple access (OFDMA), single carrier-FDMA (SC-FDMA), OFDM-FDMA, OFDM-TDMA, OFDM-CDMA, and the like.

[0057] Uplink transmission and downlink transmission may be performed based on a time division duplex (TDD) scheme that performs transmission at different times, or based on a frequency division duplex (FDD) scheme that performs transmission at different frequencies.

[0058] Also, the TDD scheme that performs transmission at different times may be used for uplink transmission and downlink transmission. Also, the FDD scheme that performs transmission at different frequencies may be used for uplink transmission and downlink transmission. Also, a half-FDD

scheme that performs uplink transmission and downlink at different frequencies and at different times may be used.

[0059] The following Table 1 may show abbreviations used in relation to the present disclosure. Here, for example, the terms disclosed in Table 1 may be identical to abbreviations used in LTE and LTE-A. Also, for example, in the following Table 1, gNB may be used to be distinguished from eNB as a base station of LTE. Here, the base station may refer to at least one of the aforementioned gNB and eNB. In the following, although the base station is used for clarity of description, the following base station may be gNB or eNB. However, it is provided as an example only.

TABLE-US-00001 TABLE 1 AS: Access Stratum BSR: Buffer Status Reporting CBR: Channel Busy Ratio CG: Configured Grant CS-RNTI: Configured Scheduling RNTI eMBB: evolved Mobile Broadband gNB: g-NodeB LCP: Logical Channel Prioritization MAC: Medium Access Control MCS: Modulation and Coding Scheme mMTC: massive Machine Type Communication RAN: Radio Access Network RLC: Radio link Control RNTI: Radio Network Temporary Identifier PDCP: Packet Data Convergence Protocol PDU: Protocol Data Unit QoS: Quality of Service RRC: Radio Resource Control TSN: Time Sensitive Networking URLLC: Ultra Reliability Low Latency Communication

[0060] Also, an NR numerology is described as an NR system. For example, the NR numerology may indicate a numerical value of a basic element or factor that generates a resource grid on a time-frequency domain for design of the NR system. For example, in a numerology of a 3GPP LTE/LTE-A system, a subcarrier spacing may correspond to 15 kilohertz (kHz) (or 7.5 kHz in the case of Multicast-Broadcast Single-Frequency Network (MBSFN)) or an extended CP. Here, the subcarrier spacing is only a single example and the meaning of the term “numerology” does not restrictively indicate only the subcarrier spacing. The meaning of the term “numerology” may include at least one of a Cyclic Prefix (CP) length, a Transmit Time Interval (TTI) length, a number of Orthogonal Frequency Division Multiplexing (OFDM) symbols within a desired time interval, and a duration of a single OFDM symbol, associated with the subcarrier spacing (or determined based on the subcarrier spacing). That is, different numerologies may be distinguished from each other based on a case in which at least one of the subcarrier spacing, the CP length, the TTI length, the number of OFDM symbols within the desired time interval, and the duration of the single OFDM symbol has a different value.

[0061] Here, for example, the NR system may use a plurality of numerologies in various scenarios, various service requirements, compatibility with a potential new system, and the like. In detail, since current numerologies of wireless communication systems may not readily support a higher frequency band, a faster movement speed, and lower latency, a new numerology may need to be defined.

[0062] For example, the NR system may support applications, such as enhanced Mobile Broadband (eMBB) that may use an ultra-wideband, massive Machine Type Communications/Ultra Machine Type Communications (mMTC/uMTC) that may use a plurality of low power devices, Ultra-Reliable and Low Latency Communications (URLLC) that requires low latency. In particular, the requirements for user plane latency on the URLLC or eMBB service may be 0.5 ms in an uplink and 4 ms in all of uplink and downlink, which may be requirements for a significant latency decrease compared to latency of 10 ms required in the 3GPP LTE and LTE-A system.

[0063] Various numerologies need to be supported to meet such various scenarios and various requirements in a single NR system. In particular, a plurality of subcarrier spacings (SCSs) may need to be supported, which differs from an aspect that a single SCS is supported in the existing LTE/LTE-A systems.

[0064] A new numerology for the NR system, which includes supporting the plurality of SCSs, may be applied to resolve an issue that a wide bandwidth is unavailable in an existing carrier or frequency range of, e.g., 700 megahertz (MHz) or 2 gigahertz (GHz). For example, an SCS may be differently determined with the assumption of a wireless communication system that operates in a carrier or a frequency range of 6 GHz or more or 40 GHz or more. However, the scope of the present disclosure is not limited thereto. That is, in the NR system, a different SCS may be configured based on a frequency domain being used, without being limited to the aforementioned example.

[0065] Also, for example, to overcome a poor channel environment, such as high pathloss, phase-noise, and frequency offset, occurring on a high carrier frequency, the NR system may use transmission of a synchronization signal, a random access signal, and a broadcast channel through a plurality of beams.

[0066] Also, the NR system may use carrier aggregation (CA). The carrier aggregation may indicate aggregating and using at least two component carriers (CCs) or cells to support a wide transmission bandwidth. Here, data packets may be transmitted or received using a single CC or a plurality of CCs depending on capability of a UE. When a carrier aggregation is configured for at least two cells, the at least two cells may include a primary cell (PCell) and at least one secondary cell (SCell).

[0067] Here, for example, in a hierarchical structure of the UE in which the carrier aggregation is configured, the UE may have a single unit MAC entity.

[0068] Meanwhile, the NR system may use a dual connectivity (DC) structure. The dual connectivity represents an operation in which the UE may simultaneously connect to a master base station and a secondary base station. The UE in which the dual connectivity is configured may have a hierarchical structure of the UE for a hierarchical structure of the master base station and a hierarchical structure of the UE for a hierarchical structure of the secondary base station.

[0069] For example, the UE in which the dual connectivity is configured may have two MAC entities, such as a MAC entity for a master cell group (MCG) that is a group of serving cells related to the master base station and a MAC entity for a secondary cell group (SCG) that is a group of serving cells related to the secondary base station.

[0070] Here, for example, when at least two cells are configured in the MCG, the at least two cells may include a PCell and an SCell. Also, when at least two cells are configured in the SCG, the at least two cells may include a primary secondary cell (PSCell) and an SCell. Here, for example, the PCell of the MCG and the PSCell of the SCG may be commonly defined as a special cell (SpCell). That is, the SpCell may represent the PCell of the MCG or the PSCell of the SCG depending on whether the MAC entity is associated with the MCG or the SCG. Hereinafter, related description is made using the SpCell based on the aforementioned description. As described above, it may represent the PCell of the MCG or the PSCell of the SCG.

[0071] Also, the NR system may use a bandwidth part (hereinafter, a BWP). For example, when the UE performs transmission and reception of a signal, a frequency bandwidth to be used may have no need to be as wide as a bandwidth of a serving cell. Here, as a BWP, the bandwidth may be configured as a narrower bandwidth than the bandwidth of the serving cell. A frequency position of the bandwidth may be shifted. Also, a bandwidth of an OFDM subcarrier may be changed. It may be defined as a partial set of the entire frequency bandwidth of the service, which may be referred to as a BWP that is a bandwidth part. However, it is provided as an example only and may apply alike if a bandwidth of a partial set is used.

[0072] In detail, FIG. 2 illustrates a method of configuring a BWP. For example, referring to FIG. 2, a serving cell may include one or more BWPs **210, 220, 230, 240, and 250**. Here, in the case of a BWP of the serving cell, information about a plurality of different BWPs may be configured in a UE by way of a base station. Each of an uplink BWP and a downlink BWP may be configured. BWP configuration information may include information about an uplink and a downlink. Also, for example, a number of BWPs activated among the aforementioned plurality of BWPs may be limited to a single BWP. Here, if the UE is capable of activating at least one BWP, the base station may verify information about a maximum number of active BWPs and may simultaneously activate a plurality of BWPs based on the verified information. Also, for example, if the UE is configured with the serving cell, a single BWP may be activated for the serving cell even without separate signaling from the base station. Here, the UE may perform initial access to the serving cell and may use the activated BWP for the initial access. Also, the UE may use the initial BWP until the UE receives UE configuration information from the base station.

[0073] Also, when the UE receives the UE configuration from the base station, the UE may be configured with a default BWP. Here, the default BWP may be configured as a relatively narrow bandwidth. If an amount of data to be transmitted and received is small, the UE may reduce battery consumption of the UE by activating the default BWP. Also, for example, unless the UE is configured with the default BWP, the UE may use the initial BWP for the same purpose. However, it is provided as an example only.

[0074] Also, for example, an activated BWP of the serving cell may be changed by another BWP depending on circumstances. This operation may be defined as BWP switching. When performing BWP switching, the UE may inactivate a current active BWP and may activate a new BWP. Here, the aforementioned BWP switching operation may be performed when the UE receives BWP switching order through Physical Downlink Control Channel (PDCCH) order from the base station. Also, for example, the aforementioned BWP switching operation may be performed through an RRC configuration. Also, for example, the aforementioned BWP switching operation may be performed through a predetermined timer “bwpInactivityTimer” as a timer for BWP inactivity. Also, for example, the aforementioned BWP switching operation may be performed in response to starting a random access. In the following, a case in which the aforementioned BWP switching occurs is described.

[0075] The base station may change an active BWP in the serving cell of the UE depending on circumstances. If the UE desires to change an active BWP, the base station may notify a BWP to be switched through a PDCCH. Here, the UE may perform the BWP switching operation through BWP switching related information included in the PDCCH.

[0076] Also, for example, the UE may perform the BWP switching operation through BWP switching related information included in an RRC message.

[0077] Also, for example, the aforementioned timer “BWPInactivityTimer” may be configured for each serving cell. Here, “BWPInactivityTimer” may be a timer for inactivating an active BWP, without being limited to the aforementioned name. That is, a timer performing the same functionality may be “BWPInactivityTimer.” In the following, although “BWPInactivityTimer” is used for clarity of description, it is provided as an example only.

[0078] Here, if the aforementioned timer expires, the UE may inactivate a current active BWP and may activate the default BWP. That is, switching may be performed using the default BWP. Also, for example, based on the aforementioned description, if the UE is not configured with the default BWP, the UE may switch to the initial BWP. Here, the UE may reduce battery consumption by monitoring a narrow bandwidth through the aforementioned switching operation. Also, a start and restart condition of the timer may be represented by the following Table 2. That is, if the UE needs to maintain an active BWP as follows, the timer may start or restart to prevent the active BWP from being inactivated.

TABLE-US-00002 TABLE 2 Downlink assignment or uplink grant reception based on PDCCH If a UE receives a downlink assignment or an uplink grant through PDCCH order, it represents that data to be transmitted and received is present and thus, a timer to maintain a current active BWP may start/ restart. MAC PDU transmission or reception If a UE transmits a MAC PDU in a configured uplink grant or receives a MAC PDU in a configured downlink assignment, MAC PDU transmission and reception may be performed without receiving separate PDCCH order in the configured uplink grant and the configured downlink assignment. Therefore, the aforementioned operation also indicates that data to be transmitted and received is present and thus, a timer to maintain a current active BWP may start/restart. In the case of performing BWP switching In the case of performing BWP switching, a timer may start/restart in a new switched BWP.

[0079] Also, for example, referring to FIG. 2, at least one of a size of a frequency bandwidth used in a frequency domain, a subcarrier spacing length, and a length of time occupied in a time domain may be differently configured in a BWP. For example, in FIG. 2, a size of a frequency bandwidth, a subcarrier spacing length, and an occupancy time length of each of the BWPs 210, 220, 230, 240, and 250 may be differently configured based on BWP configuration information. However, it is provided as an example only.

[0080] Also, a random access resource may be configured for each BWP of a serving cell. That is, a configuration of a random access resource may be different for each BWP. Therefore, if the UE desires to perform random access, a case in which a random access resource is not configured in a current active BWP may be considered. Here, for example, the UE may autonomously switch to an initial BWP and start the random access without order from the base station. In detail, as described above, since the initial BWP may be configured for the initial access, the random access resource may be configured in the initial BWP at all times. Therefore, if the UE verifies that there is no random access resource in an active BWP, the UE may switch to the initial BWP and may perform a random access procedure without separate signaling.

[0081] As described above, an NR system may support a service that requires low latency and high reliability, such as URLLC, through supporting of various numerologies. Here, for example, a use case about high requirements may be considered as a current low latency and high reliability service. For example, at least one use case among entertainment industry using augmented reality (AR) or virtual reality (VR), factory automation, transportation industry, and power distribution may be considered. Here, the aforementioned use case may further improve requirements about low latency and high reliability in providing a service. Therefore, in the NR system operations of a UE and a base station that aim further enhanced URLLC may need to be defined. For example, the aforementioned definition may be referred to as NR Industrial Internet of Things (IIoT). However, it is provided as an example only. For clarity of description, definition to meet the further enhanced requirements in the NR system is hereinafter referred to as IIoT.

[0082] The IIoT may support frequency range 1 and frequency range 2 based on the existing NR system. Also, the IIoT meets the requirements about URLLC that may use both TDD and FDD based on the existing NR system. For example, the IIoT may require a design to meet high reliability requirements of a data duplication and multi-connectivity enhancements service. For example, in the case of PDCP duplication, enhancements may be considered to generate a maximum of four copies. Here, if a number of copies increases, a resource use may increase. Therefore, enhancements of a PDCP duplication method may be considered to efficiently use resources. For example, a PDCP duplication may be selectively performed for each packet, not based on a radio bearer (RB). Also, for example, a PDCP duplication activity/inactivity method may be considered as enhancements. However, it is provided as an example only.

[0083] Also, for example, UL/DL intra-UE prioritization/multiplexing may be considered. In detail, if DL/UL radio resources collide between control and/or data traffic related to different QoS requirements, the UE may solve the aforementioned radio resource collision through an intra-UE prioritization and multiplexing method. For example, the radio resource collision may occur when designating priority for a downlink in the UE. In detail, the downlink in the UE may be prioritized. The UE may correspond to different DL assignments that are sequentially received. Radio resources for DL assignments may temporally overlap. Here, the UE may receive DL traffic through prioritization between DL assignments. As another example, a case of prioritizing an uplink in the UE may be considered. Here, a collision between a configured grant and a dynamic allocated grant may occur. A dynamic allocated grant received by the UE for uplink transmission may overlap on a time with a configured grant for type 1 or type 2.

[0084] Here, the dynamic allocated grant of the exiting UE may have higher priority than that of the configured grant at all times. Here, the NR IIOT may need to meet the requirements by focusing on URLLC traffic and thus, may need to operate in a different manner from an existing operation. Therefore, if a collision occurs between the configured grant and the dynamic allocated grant, the UE may perform UL traffic transmission using a single grant through prioritization. Also, for example, a case of prioritizing an uplink in the UE may be considered. Here, a collision may occur between configured grants. For example, in IIoT, configured grants for different services and/or traffic types may be configured in given BWPs of the serving cell. For example, a configured grant may be configured for improvement in stability and decrease in a waiting time in the IIoT. Herein, in the case of the existing UE, a single configured grant may be configured in a given BWP. Therefore, if a plurality of configured grants is configured in the BWP, the plurality of configured grants may overlap on a time axis.

[0085] In detail, the UE may simultaneously support services and/or traffic types for different requirements. Here, a configured grant may be configured for each service and/or traffic type. Therefore, a collision may occur between a plurality of configured grants according to the respective services and/or traffic types.

[0086] As another example, the UE may configure a plurality of configured grants to support a plurality of periodic TSN flows. Here, a period and an offset may differ for each flow. Therefore, the UE may configure a configured grant for each TSN flow. As described above, a collision may occur between the configured grants.

[0087] As another example, a plurality of configured grants may be configured to support a single service such as TSN. Here, in the TSN, a period of

a data packet may differ according to an application. Also, in the TSN, the period of the data packet may not be a multiple of a slot or a symbol period. As described above, the plurality of configured grants may need to be configured. Also, if the plurality of configured grants is configured, a collision may occur between the configured grants. As another example, if an uplink in the UE is prioritized, a collision may occur between dynamic allocated grants. In detail, the UE may sequentially receive, from the base station, a plurality of dynamic approvals for uplink transmission using temporally overlapping Physical Uplink Shared Channel (PUSCH) resources. Here, in view of the aforementioned circumstance, the UE may need to process priority between a plurality of grants. For example, a case in which a collision occurs between control information and control information may be considered as a case in which an uplink in the UE is prioritized. Here, the UE may simultaneously trigger transmission of control information (e.g., SR, HARQ feedback, CSI) about traffic having high priority and transmission of control information about traffic having low priority. Here, the UE may need to process the priority between a plurality of grants.

[0088] Also, for example, a case in which an uplink in the UE is prioritized and a grant collision occurs between control information and data may be considered. For example, the UE may simultaneously trigger transmission of control information (e.g., SR, HARQ feedback, CSI) about traffic having high priority and data transmission about traffic having low priority. Here, the UE may need to process the priority between a plurality of grants.

[0089] Also, for example, enhancements to meet requirements may be required into consideration of TSN related enhancements. For example, the TSN may refer to technology that provides a low latency and low packet loss service based on Ethernet of Layer 2 (L2). Here, the TSN may represent technology that may reduce latency occurring between the UE and the base station by synchronizing time between components sharing network resources and by processing traffic based on the synchronized time.

[0090] For example, TSN enhancements may be required in the IIoT to support a use case such as motion control. Here, the motion control may target reliability of 99.9999% or more and may target clock synchronization of within 1 microsecond, and latency of within 0.5 ms. However, it is provided as an example only and the present disclosure is not limited to the aforementioned example. Therefore, to meet the requirements, a method of forwarding accurate reference timing may be required in the NR IIoT. Also, to meet the requirements, the NR IIoT may require QoS/scheduling enhancement for meeting low latency and high reliability requirements. Also, the NR IIoT may use Ethernet header compression technology for reducing overhead in a packet transmission. However, it is provided as an example only.

[0091] Hereinafter, an operation in a case in which a collision occurs between configured grants is described based on the aforementioned description.

[0092] Here, as described above, in the IIoT, a configured grant may be configured in the UE as a transmission grant to support a URLLC service. Here, the configured grant may indicate that a base station configures in advance a transmission grant to be used by a UE in the UE. In detail, to meet service requirements that request low latency and high reliability, the base station may preconfigure a configured grant in the UE.

[0093] If data to be transmitted is present, the UE may perform data transmission through the configured grant without requesting the base station for an uplink grant. Here, two types of configured grants may be present in the NR. For example, type 1 (configured grant type 1) may be configured through an RRC reconfiguration message. Here, type 1 may be configured for each BWP of each carrier. For example, a configured grant based on type 1 may be valid as a configured grant although the UE does not currently use a BWP of a carrier in which the configured grant type 1 currently configured. Therefore, if the UE selects a BWP configured based on type 1 as the configured grant, the UE may perform data transmission by immediately using the grant without performing an additional operation. That is, the UE may meet low latency requirements of a service by transmitting data immediately using the configured grant at the very moment of selecting the BWP of the carrier in which the configured grant type 1 is configured.

[0094] As another example, the configured grant type 1 may be configured for the purpose of URLLC data transmission. For example, configured grant type 1 of the UE may be configured for each logical channel. That is, the UE may transmit data using the configured grant only for a logical channel capable of using the configured grant type 1. That is, as described above, whether the configured grant type 1 is available may be set to the logical channel.

[0095] As another example, the configured grant type 1 may be shared with another UE. As described above, the UE may repeatedly transmit the same data several times to increase a transmission probability even at an occurrence of a collision. Also, for example, if the UE transmits data using the configured grant type 1, the UE may operate based on configuredgrantTimer. For example, the UE may wait for Hybrid Automatic Repeat and Request (HARQ) feedback during operation of a timer. Here, if the timer expires, the UE may discard data stored in an HARQ buffer and may transmit another data. That is, the timer may operate based on an HARQ process.

[0096] On the contrary, type 2 (configured grant type 2) may be a configured grant that is dynamically configured through a PDCCH. For example, type 2 may be valid only in a BWP of a carrier currently being used. That is, as described above, the UE may transmit data without causing latency for a transmission grant selection process based on the configured grants of type 1 and type 2.

[0097] Also, for example, the configured grant type 2 may be configured for the purpose of periodic data transmission. Here, the UE may transmit data using the configured grant type 2 and may activate or inactivate by the PDCCH.

[0098] Here, since the NR IIoT requires low latency and high reliability, all of configured grants of type 1 and type 2 may be used in view of the aforementioned requirements. Also, for example, to support different services and/or a single service, a plurality of configured grants may be configured in a single BWP. It is further described below.

[0099] Here, for example, as described above, the NR IIoT may support a plurality of configured grants to meet strict requirements of the URLLC service. Here, if the plurality of configured grants is configured, a collision may occur between the configured grants. Here, if the collision occurs between the configured grants, the UE may select a specific configured grant from among the colliding configured grants. Also, a network configuration may be defined based on the collision between the configured grants. In the following, a method of performing transmission by selecting a most appropriate configured grant if a collision occurs between configured grants is described. Also, a method of guaranteeing transmission for the UE to retransmit dropped data due to a collision between configured grants is described. Here, the following configuration may expandable apply to not only the aforementioned circumstance but also similar fields as a case of a grant collision, without being limited to the aforementioned example.

[0100] As described above, if a collision occurs between configured grants, the UE may select a specific grant from among the colliding configured grants and may perform transmission.

[0101] For example, the UE may perform transmission through a plurality of configured grants to support different URLLC services and/or traffic types. As another example, to support a single service such as the aforementioned TSN, the UE may perform transmission using the plurality of configured grants. Here, for example, in the TSN, a period of a data packet may differ according to an application. Also, in the TSN, a transmission period of the data packet may not be a multiple of a slot or a symbol period. For example, the data packet may be generated based on an application layer and thus, may not be a multiple of the slot or symbol period. However, it is provided as an example only. Here, the UE may need to perform data transmission through the plurality of configured grants. For example, since the transmission period of the data packet is not a multiple of the slot or symbol period for the same service, the UE may configure the plurality of configured grants and may perform transmission.

[0102] Here, for example, in addition to the aforementioned cases, a plurality of configured grants may be configured in the UE. That is, the following description may relate to a UE operation and a network configuration for a case in which the plurality of configured grants is configured in the UE and the plurality of configured grants collides and is not limited to a method of configuring the plurality of configured grants.

[0103] The base station may configure a configured grant in the UE. In detail, the base station may configure a plurality of type 1 (configured grant type 1) grants in the UE through an RRC message (or RRC reconfiguration message). Also, for example, as described above, the base station may

configure a plurality of type 1 and/or type 2 grants in the UE through a PDCCH. Also, for example, the base station may configure all of type 1 and type 2 in the UE through the RRC message (or RRC reconfiguration message). However, it is provided as an example only.

[0104] Here, if the base station configures type 1 and/or type 2 grants in the UE, the base station may configure a UE ID, CS-RNTI, used for HARQ retransmission in the UE. Here, for example, the base station may configure parameters of the following Table 3 for each configured grant. For example, the parameters of the following Table 3 may include at least one of “periodicity” that is period information, “timeDomainOffset” that is time domain offset information, “timeDomainAllocation” that is time domain allocation information, and “nrofHARQ-Processes” that is information about a number of HARQ processes. In detail, “periodicity” may represent a period of a configured grant. Here, for example, as described above, a period may be indicated for each configured grant. Also, “timeDomainOffset” may represent a resource offset about “SFN (System Frame Number)=0.” Also, “timeDomainAllocation” may be resource allocation information configured in a time domain. For example, “timeDomainAllocation” may include “startSymbolAndLength.” Also, “nrofHARQ-Processes” may represent a number of HARQ processes for a configured grant. Also, for example, the base station may configure information aside from information of the following Table 3 in the UE. However, it is provided as an example only.

TABLE-US-00003

TABLE 3	periodicity	timeDomainOffset	timeDomainAllocation	nrofHARQ-Processes
---------	-------------	------------------	----------------------	--------------------

[0105] Here, for example, the base station may not configure “timeDomainOffset” and “timeDomainAllocation” for type 2. Also, for example, the CS-RNTI may be used for retransmission with respect to type 2. Also, the CS-RNTI may be used to indicate activity or inactivity of a grant for type 2. Also, for example, the base station may allocate a grant such that a different HARQ process may be used for each configured grant.

[0106] Here, if the configured grant type 1 is configured in the UE, an N^{sup.th} configured grant may be configured in the UE according to the following Equation 1. For example, if the configured grant type 1 is configured in the UE, the UE may verify a symbol in which the N^{sup.th} configured grant is configured. Here, for example, in the following Equation 1, S denotes a start symbol of a slot. Also, “periodicity” may be the aforementioned parameter. That is, the UE may verify a grant for type 1 among configured grants configured by the base station through the following Equation 1. However, it is provided as an example only.

[00001]

$$[(SFN \times \text{numberOfSlotPerFrame} \times \text{numberOfSymbolsPerSlot}) + (\text{slotnumberinthe frame} \times \text{numberOfSymbolsPerSlot}) + \text{symbolnumberintheslot}] = (\text{timeDomainOffset} + \text{timeDomainAllocation}) \times \text{periodicity}$$

[0107] As another example, if the configured grant type 2 is configured in the UE, the UE may verify a symbol in which a configured grant is configured according to the following equation 2. That is, the UE may verify a grant for type 2 among configured grants configured through the base station according to the following Equation 2. However, it is provided as an example only.

[00002]

$$[(SFN \times \text{numberOfSlotPerFrame} \times \text{numberOfSymbolsPerSlot}) + (\text{slotnumberinthe frame} \times \text{numberOfSymbolsPerSlot}) + \text{symbolnumberintheslot}] = [(SFN \times \text{numberOfSlotPerFrame} \times \text{numberOfSymbolsPerSlot}) + (\text{slotnumberinthe frame} \times \text{numberOfSymbolsPerSlot}) + \text{symbolnumberintheslot}] \times \text{periodicity}$$

[0108] As another example, if the UE uses a configured grant, the UE may perform an HARQ process. Here, an HARQ process ID related to a case in which the UE uses the configured grant may be induced according to the following Equation 3. Here, for example, “periodicity” and “nrofHARQ-processes” may be verified through the aforementioned parameters. However it is provided as an example only.

[00003] HARQProcesID = [floor(CURRENT_symbol / periodicity)]modulonrofHARQ - Processe [Equation3]

[0109] Also, for example, in Equation 3, CURRENT_symbol/periodicity may be induced according to the following Equation 4.

[00004]

$$\text{CURRENT}_{\text{symbol}} = (SFN \times \text{numberOfSlotsPerFrame} \times \text{numberOfSymbolsPerSlot} + \text{slotnumberinthe frame} \times \text{numberOfSymbolsPerSlot} + \text{symbolnumberinthe slot}) \times \text{periodicity}$$

[0110] Here, “numberOfSlotsPerFrame” and “numberOfSymbolsPerSlot” may represent a number of consecutive slots per frame and a number of consecutive symbols per slot, respectively. However, it is provided as an example only.

[0111] Here, according to the aforementioned operation, a plurality of configured grants may be configured in the UE. For example, as described above, a plurality of configured grants may be configured in the UE. Here, if a collision occurs between the plurality of configured grants configured in the UE, the UE may select a specific grant from among the plurality of configured grants.

[0112] In detail, referring to FIG. 3, configured grant 1 (Configuration Grant 1, CG1) and configured grant 2 (Configuration Grant 2, CG2) may be configured in the UE. However, it is provided as an example only and is not limited to the aforementioned example.

[0113] Each configured grant configured in the UE may be transmitted at a different period. Here, although each configured grant has a different period, PUSCH transmission intervals about the respective configured grants may partially overlap. For example, referring to FIG. 3, PUSCH transmissions about CG1 and CG2 configured in the UE may overlap at t₀. That is, a grant 310 for CG1 and a grant 320 for CG2 may overlap at a time t₀. Here, the UE needs to select a single grant from among the grant 310 for CG1 and the grant 320 for CG2. That is, if a plurality of configured grants is configured in the UE, the UE may select a single configured grant from among the plurality of configured grants and may perform transmission based on the selected configured grant.

[0114] Here, for example, the plurality of configured grants configured in the UE may be prioritized. For example, if a collision occurs between the plurality of configured grants, the UE may select a configured grant having high priority from among the plurality of configured grants and may perform transmission.

[0115] As another example, if a collision occurs between the plurality of configured grants, the UE may select a temporally preceding configured grant from among the plurality of configured grants. That is, the UE may select the temporally preceding configured grant regardless of the priority and may perform transmission.

[0116] As another example, if a collision occurs between the configured grants, the UE may verify whether it relates to the same service. However, it is provided as an example only. For example, the plurality of configured grants may be configured in the UE to support different services. Here, the collision may occur between the plurality of configured grants for supporting different services. Here, the UE may select a configured grant for a service having high priority based on the priority of each service.

[0117] As another example, the plurality of configured grants may be configured to support a single service. Here, a collision may occur between the plurality of configured grants configured in the UE. Here, the UE may select a temporally preceding configured grant. That is, in the case of selecting a single configured grant, the UE needs to determine whether the configured grants relate to the same service or different services. Here, if the plurality of configured grants is configured in the UE for the same service, the UE may select a temporally preceding configured grant. Also, for example, if the plurality of configured grants is configured in the UE for different services, the UE may select a configured grant having high priority from among the configured grants.

[0118] The UE may need to internally exchange information about occurrence or non-occurrence of a collision between configured grants and/or information about priority for the aforementioned operation. In detail, a MAC entity of the UE may include an entity (e.g., an HARQ entity and a multiplexing and assembly entity) in charge of each role and may perform a function (e.g., uplink grant reception, LCP, MAC PDU configuration). Here, for example, referring to FIG. 4, a MAC entity 410 of the UE may verify a received grant through an uplink grant reception function. Here, the MAC entity 410 of the UE may identify HARQ information and an HARQ process ID of the corresponding grant. Next, the MAC entity 410 of the UE may forward information about an uplink grant and HARQ information to an HARQ entity 420 of the UE. Here, the HARQ entity 420 of the UE may forward information for acquiring a MAC PDU to a multiplexing and assembly entity 430 of the UE with respect to the corresponding HARQ process ID through the received information. Here, the multiplexing and assembly entity 430 of the UE may perform LCP for performing a data transmission through the aforementioned grant. Here, the LCP may indicate selecting a logical channel to transmit data using the grant. Also, the multiplexing and assembly entity 430 of the UE may configure the MAC PDU by performing multiplexing of data (MAC SDU) received from the

selected logical channel. Here, the HARQ entity 420 of the UE may store the MAC PDU in a corresponding process ID based on HARQ information and the HARQ process ID of the received grant. Next, the UE may perform data transmission based on the HARQ information. That is, each entity of the UE may perform each corresponding functionality for the data transmission. Here, for example, each entity of the UE may be unaware of information of another entity. Therefore, information required for processing may need to be exchanged between the respective entities. For example, an uplink grant reception entity may verify available grant information. Here, the uplink grant reception entity may be unaware of a logical channel of which data is to be transmitted through the corresponding grant. Also, for example, the LCP may select a logical channel to be transmitted through the corresponding grant, but may be unaware of information about whether a collision occurs between grants and a subsequent available transmission time.

[0119] Here, if a collision occurs between the plurality of configured grants configured in the UE, a service for each grant and prioritization for the service may be performed through an LCP process. Here, whether the collision occurs between the plurality of configured grants may be verified through an uplink grant reception function of the UE. Considering this, the UE needs to internally exchange information. In detail, the UE may verify whether the collision occurs between the plurality of configured grants through the uplink grant reception function. Here, the UE may not verify a logical channel of which data is transmitted in the corresponding grant. That is, the UE may be unaware of a service to which logical channel data of the corresponding grant corresponds. Therefore, the UE may not compare priority between the configured grants and may not verify which configured grant the UE needs to select.

[0120] Therefore, the UE may need to provide information about occurrence of the collision such that the LCP may select a single configured grant through service and priority comparison. Also, the LCP needs to provide priority information such that the HARQ entity may transmit a MAC PDU having higher priority, which is described below.

[0121] Here, for example, referring to FIG. 5, a UE may perform uplink data transmission. In detail, referring to (a) of FIG. 5, the UE may induce an HARQ process ID associated with a PUSCH transmission interval about each activated configured grant based on the aforementioned Equation 3 and Equation 4. Here, for example, if “configuredGrantTimer” is not in an operating state for a corresponding HARQ process, the UE may determine that a new data indicator (NDI) is toggled for the corresponding HARQ process. Here, a MAC entity 510 of the UE may forward a configured grant and related HARQ information to an HARQ entity 520 to transmit new data. Here, the NDI may be a parameter value used to indicate whether a packet is initial transmission or retransmission of the corresponding HARQ process. Here, if the NDI is toggled, the UE may perform the initial transmission. On the contrary, unless the NDI is toggled, the UE may perform the retransmission. Here, for example, if “configuredGrantTimer” does not operate, the UE may not perform the retransmission anymore. Therefore, the UE may determine that the NDI is toggled and may perform new transmission.

[0122] Here, the HARQ entity 520 may identify an HARQ process about a corresponding grant through the configured grant and HARQ information received from the MAC entity 510. Here, the HARQ entity 520 may acquire a MAC PDU to be transmitted using the identified HARQ process from a multiplexing and assembly entity 530.

[0123] Here, for example, the multiplexing and assembly entity 530 may perform LCP. Next, the multiplexing and assembly entity 530 may configure a MAC PDU based on the LCP. For example, the LCP may be a process of selecting an appropriate logical channel based on a transmission grant allocated in an uplink grant and selecting an amount of data to be transmitted for each selected logical channel. Therefore, if the UE performs new transmission, the UE may select data to be transmitted based on each transmission grant by performing the LCP. Here, for example, to control scheduling of uplink data, the base station may provide the UE with a parameter about at least one of “priority,” “prioritisedBitRate,” and “bucketSizeDuration” for each logical channel. Here, the UE may perform a configuration for each logical channel based on the parameter received from the base station. Here, for example, “priority” may represent priority of each logical channel. For example, the higher a “priority” value, the lower priority. Also, “prioritisedBitRate (PBR)” may represent a prioritized bit rate. Also, “bucketSizeDuration” may represent a bucket size duration time. Also, for example, the base station may additionally configure a parameter about a mapping limit to each logical channel. Here, the aforementioned parameter may be at least one of “allowedSCS-List,” “maxPUSCH-Duration,” “configuredGrantType1Allowed,” and “allowedServingCells.” Here, “allowedSCS-List” may represent a subcarrier spacing in which transmission is allowed. Also, “maxPUSCH-Duration” may represent a maximum PUSCH duration time allowed for transmission. Also, “allowedServingCells” may represent a cell in which transmission is allowed. Also, subcarrier spacing information, PUSCH transmission duration information, and cell information may be included in each uplink grant. Therefore, the UE may select a logical channel that meets the aforementioned condition based on transmission information of the uplink grant. Meanwhile, for example, “configuredGrantType1Allowed” may represent whether data of a corresponding logical channel may be transmitted using configured grant type 1. That is, if the uplink grant is configured grant type 1, the UE may select only a logical channel in which “configuredGrantType1Allowed” is set to “true.”

[0124] Here, for example, as described above, a plurality of configured grants may be configured in the UE and a collision may occur between the plurality of configured grants. Here, if the collision occurs between the configured grants, the MAC entity 510 may forward collision indication information to the HARQ entity 520. Next, the HARQ entity 520 may forward information about the uplink grant and collision indication information to the multiplexing and Assembly entity 530. That is, as described above, since each of entities in the UE is unaware of information about functions performed by other entities, information related thereto needs to be forwarded. Here, even the MAC entity 510 of the UE may forward corresponding information to notify the HARQ entity 520 of information about the collision. Also, the HARQ entity 520 may transmit corresponding information to the multiplexing and Assembly entity 530 that constitutes the MAC PDU.

[0125] Here, if the same logical channel is selected with respect to configured grants between which a collision occurs, the UE may be aware that the corresponding collision relates to a collision between the configured grants for the same service. Here, for example, the UE may determine to select and use a temporally preceding grant from among the colliding configured grants. That is, as described above, if the plurality of configured grants is configured for the same service and the collision occurs between the configured grants, the UE may select and use the temporally preceding grant from among the colliding configured grants. Through this, the UE may prevent latency from occurring with respect to the same service. Meanwhile, for example, the UE may configure a MAC PDU for a temporally preceding configured grant such that data may be transmitted through the corresponding grant. On the contrary, the UE may not configure a MAC PDU for a configured grant that does not temporally precede.

[0126] As another example, referring to (b) of FIG. 5, if different logical channels are selected with respect to configured grants between which a collision occurs, the UE may verify that the corresponding collision relates to a collision between the configured grants for the different services. Here, the MAC entity 510 of the UE may forward collision indication information to the HARQ entity 520. Next, the HARQ entity 520 may forward information about the uplink grant and collision indication information to the multiplexing and Assembly entity 530. That is, as described above, since each of entities in the UE is unaware of information about functions performed by other entities, information related thereto needs to be forwarded. Here, even the MAC entity 510 of the UE may forward corresponding information to notify the HARQ entity 520 of information about the collision. Also, the HARQ entity 520 may transmit corresponding information to the multiplexing and Assembly entity 530 that configures the MAC PDU.

[0127] As described above, the UE may compare priority between logical channels for the respective grants through the LCP process. Here, the UE may select a logical channel having higher priority and a configured grant for the logical channel and may perform transmission. That is, the UE may configure a MAC PDU based on a logical channel having higher priority and a configured grant thereof.

[0128] For example, even using a logical channel having low priority and a configured grant thereof, the UE may configure a MAC PDU. Here, in the case of configuring the MAC PDU for each configured grant, the multiplexing and assembly entity 530 of the UE may provide priority information about the MAC PDU to the HARQ entity 520 of the UE. Here, the HARQ entity 520 may receive the aforementioned priority

information and the MAC PDU and may store the same in an HARQ buffer. Here, the HARQ entity 520 may perform transmission for the MAC PDU having higher priority.

[0129] Also, for example, if different logical channels are selected grants between which a collision occurs, the UE may determine to select and use a temporally preceding grant from among the colliding configured grants. That is, as described above, if a plurality of configured grants is configured with respect to different services and a collision occurs between the configured grants, the UE may select and use the temporally preceding grant from among the colliding configured grants. Therefore, the UE may select and use a temporally preceding grant for a different service. However, it is provided as an example only. Meanwhile, for example, the UE may configure a MAC PDU for a temporally preceding configured grant such that data may be transmitted through the corresponding grant. On the contrary, the UE may not configure a MAC PDU for a configured grant that does not temporally precede. That is, if the collision occurs between the configured grants, the UE may perform transmission for a temporally preceding grant regardless of whether the configured grants relate to the same service. However, it is provided as an example only.

[0130] Meanwhile, as described above, if the collision occurs between the configured grants, the UE may select a single grant and may perform transmission using the selected grant. Here, for example, if a collision occurs between configured grants that are configured for a single service, the base station may expect to select and use a single transmission grant. Here, for example, if a plurality of configured grants is configured to support different services, all of the plurality of configured grants may target an URLLC service. That is, as described above, as a case in which the plurality of configured grants is configured to secure low latency and high reliability, if a collision occurs, the UE may need to guarantee data transmission for a dropped configured grant based on priority. For example, the base station may allocate a retransmission grant to CS-RNTI of the UE to guarantee transmission of data of which transmission is omitted. It is further described below.

[0131] FIG. 6 illustrates an operation of a UE according to the present disclosure. Referring to FIG. 6, a plurality of configured grants may be configured in the UE. Here, the configured grants may be configured based on different periods. For example, if a collision occurs between the plurality of configured grants, the UE may select a temporally preceding grant from among the configured grants and may perform transmission. Here, the UE may configure a MAC PDU for the temporally preceding grant and may not configure a MAC PDU for a sub sequent grant in which the collision occurs. That is, referring to FIG. 6, a grant 610 for configured grant 1 (CG1) and a grant 620 for configured grant 2 (CG2) may collide at a time t_0 . That is, a first collision may occur between the plurality of configured grants configured in the UE at the time t_0 . Here, the UE may configure a MAC PDU for the temporally preceding CG1 and may store the same in a corresponding HARQ process and may not configure a MAC PDU for CG2 in which the collision occurs. Also, for example, a grant 630 for CG1 and a grant 640 for CG2 may collide at a time t_1 . That is, a second collision may occur between the plurality of configured grants configured in the UE at the time t_1 . Here, the UE may configure a MAC PDU for the temporally preceding CG2 and may store the same in a corresponding HARQ process and may not configure a MAC PDU for CG1 in which the collision occurs. That is, the UE may configure a MAC PDU for a temporally preceding configured grant and may not configure a MAC PDU for a configured grant that does not temporally precede at each collision point in time. Here, for example, the aforementioned description may apply to a case in which a plurality of configured grants is configured for the same service. For example, as described above, the reason why the plurality of configured grants is configured for the same service may be to support a period of a data packet that is not transmitted at a multiple of a symbol and/or slot period in TSN. As described above, if configured grants are configured for the same service, a base station may be aware of a point in time at which a collision occurs between the grants. Here, since the grants relate to the same service, the UE may select a temporally preceding single grant and perform transmission, which may lead to reducing latency of packet transmission. Therefore, the UE may configure a MAC PDU for the temporally preceding grant. For example, in the case of configuring a MAC PDU, the UE may select an appropriate logical channel based on transmission grant information through an LCP process. Here, a transmission grant corresponding to a PBR value set to a logical channel may be allocated to a corresponding logical channel starting from a logical channel having top priority based on the selected logical channel. Next, if a grant remains, the UE may allocate a grant to a corresponding logical channel based on priority of the selected logical channel until all of an uplink grant or data of the corresponding logical channel is consumed. The UE may configure a MAC SDU based on the allocated grant such that available data may be transmitted to each logical channel. Next, the UE may configure a single MAC PDU by multiplexing MAC SDUs configured from the respective logical channels. As described above, if the UE configures a MAC PDU, an HARQ entity of the UE may store the MAC PDU, an uplink grant, and HARQ information in a corresponding HARQ process. Next, an HARQ entity of the UE may indicate the identified HARQ process to trigger new transmission. Here, if the aforementioned uplink grant is a configured grant and if the UE performs transmission for the HARQ process, “configuredgrantTimer” may start or restart. The UE may expect to perform retransmission for the MAC PDU stored in the corresponding HARQ during the operation of “configuredgrantTimer.” On the contrary, the HARQ entity may determine that there is no data to be transmitted for a grant for which a MAC PDU is not acquired and may not perform transmission. That is, in FIG. 6, the UE may select the temporally preceding CG1 at the first collision out of two collisions. On the contrary, at the second collision, the UE may select the temporally preceding CG2 and may perform transmission. However, it is provided as an example only.

[0132] Also, for example, although description is made based on a case in which the plurality of configured grants is configured for the same service, the plurality of configured grants may be configured for different services. In this case, the UE may perform transmission through a temporally preceding configured grant. However, it is provided as an example only.

[0133] Also, FIG. 7 illustrates an operation of a UE according to the present disclosure. For example, referring to FIG. 7, a plurality of configured grants may be configured in the UE. Here, a collision may occur between the plurality of configured grants configured in the UE. Here, the UE may determine priority for the plurality of configured grants based on the aforementioned description. That is, a specific configured grant may have high priority among the plurality of configured grants. Here, as described above, the UE may configure a MAC PDU for the configured grant having high priority and may perform transmission. Meanwhile, for example, as described above, the UE may configure a MAC PDU for the configured grant of which transmission is omitted. For example, an HARQ entity of the UE may transmit a MAC PDU corresponding to high priority based on priority information provided through LCP. On the contrary, an HARQ entity of the UE may not transmit a MAC PDU corresponding to low priority. Here, even with respect to a MAC PDU of which transmission is omitted, the UE may expect to perform transmission using a retransmission grant addressed to CS-RNTI. For example, the UE may perform retransmission for a MAC PDU of which transmission is omitted through the aforementioned grant addressed to the CS-RNTI. Therefore, the UE may need to start “configuredgrantTimer” for the MAC PDU of which transmission is omitted. That is, although the UE does not perform transmission, the UE may expect to receive a retransmission grant by starting “configuredgrantTimer” in a transmission interval of the corresponding grant. In response to receiving the retransmission grant, the UE may immediately transmit the configured MAC PDU. In detail, as described above, if “configuredgrantTimer” is not in an operating state for a corresponding HARQ process, the UE may determine that an NDI for the corresponding HARQ process is toggled and may transmit new data. Alternatively, if “configuredgrantTimer” is not in the operating state for the corresponding HARQ process, the UE may ignore an uplink grant received using CS-RNTI. The UE may receive a grant for retransmission and perform the retransmission only while “configuredgrantTimer” operates. Therefore, if the aforementioned “configuredgrantTimer” does not operate, the UE may ignore the uplink grant received using the corresponding CS-RNTI and may not perform transmission. That is, if “configuredgrantTimer” is not in the operating state, the UE may not perform retransmission anymore. In view of the aforementioned aspect, the UE may start “configuredgrantTimer” to perform retransmission for a MAC PDU of which transmission is omitted. Here, if the UE receives a retransmission grant using CS-RNTI, the UE may immediately perform transmission without performing additional processing for configuring the MAC PDU, which may be advantageous in terms of decreasing latency. Here, for example, in association with the aforementioned operation, the plurality of configured grants may relate to different services. That is, for different services, the UE may need to perform retransmission for a corresponding service for URLLC, which differs from a case in which the plurality of configured grants relates to the same service. If the plurality of configured grants relates to different services in view of the aforementioned aspect,

the UE may configure a MAC PDU and may start “configuredgrantTimer” although transmission is omitted.

[0134] Also, for example, since retransmission may be performed even for the same service, the UE may configure the MAC PDU and may start “configuredgrantTimer” although transmission is omitted, without being limited to the aforementioned example.

[0135] As another example, the UE may configure a MAC PDU only for a logical channel (LCH) and a grant having high priority. Here, for example, the HARQ entity may perform MAC PDU transmission only for an HARQ process for which a MAC PDU is acquired.

[0136] Here, for example, if a plurality of configured grants is configured to support different services, a dropped configured grant may also target a URLLC service. Therefore, the UE may need to guarantee transmission even for data that is not transmitted due to priority. Here, for example, to guarantee transmission of data of which transmission is omitted, the base station may allocate a transmission grant to C-RNTI of the UE. However, it is provided as an example only.

[0137] In detail, for example, referring to FIG. 7, a collision may occur between a grant **710** for configured grant **1** (CG1) and a grant **720** for configured grant **2** (CG2) at a time **t0**. Here, for example, priority of CG1 may be higher than that of CG2. Therefore, the UE may configure a MAC PDU for CG1 and may perform transmission at the time **t0**. Meanwhile, the UE may configure a MAC PDU for CG2. That is, the UE may configure the MAC PDU for CG2 of which transmission is omitted. Also, the UE may start “configuredgrantTimer” for the MAC PDU for CG2. Next, the UE may receive an allocation of a grant **730** for retransmission from a base station based on CS-RNTI. Here, the UE may perform the MAC PDU for CG2 through the grant **730** allocated for retransmission. However, it is provided as an example only.

[0138] Also, for example, referring to FIG. 8, a plurality of configured grants may be configured in a UE. As describe above, the UE may verify a configured grant having high priority. Here, the UE may configure a MAC PDU only for the configured grant having high priority and may perform transmission. That is, the UE may not configure a MAC PDU for a grant of which transmission is omitted as a configured grant having low priority. Here, an HARQ entity may perform MAC PDU transmission only for an HARQ process for which a MAC PDU is acquired. Here, for example, the UE may transmit data of which transmission is omitted and thus that is dropped using an uplink grant addressed to C-RNTI. In detail, the UE may expect to transmit data of which transmission is omitted and that is dropped using the uplink grant addressed to C-RNTI. Here, as described above, the UE may store the configured MAC PDU in the corresponding HARQ process through LCP and MAC PDU configuration process for the uplink grant addressed to C-RNTI and then may perform transmission. Therefore, dissimilar to the example of FIG. 7, in the case of performing retransmission for a grant of which transmission is omitted, the UE may perform an additional procedure and then perform transmission. Therefore, transmission may be delayed. Here, for example, the UE may require transmission of data that is additionally generated at a point in time at which the UE transmits data for a configured grant of which transmission is omitted. Therefore, dissimilar to the example of FIG. 7, the UE may not configure a MAC PDU for a configured grant of which transmission is omitted at a collision point in time. Next, as described above, the UE may store the configured MAC PDU in the corresponding HARQ process through the LCP and MAC PDU configuration process and then may perform transmission. However, it is provided as an example only.

[0139] As another example, if the UE performs transmission using a dynamic allocated uplink grant through a PDCCH, a parameter “configuredgrantAllowed” may not be applied. That is, if the UE performs retransmission for a grant of which transmission is omitted, the UE may transmit even other data in addition to URLLC data. That is, based on the aforementioned circumstance, if the UE performs retransmission for data of which transmission is omitted, additional limit may be configured in the UE to guarantee URLLC data transmission. For example, a case in which the UE receives an uplink grant addressed to C-RNTI may be considered as a case in which a collision occurs between configured grants. Here, if an HARQ process ID of the corresponding uplink grant is identical to an HARQ process ID of data of which transmission is omitted, the UE may configure a MAC PDU for data of which transmission is omitted and that is dropped as described above, and may preferentially transmit the dropped data. Here, for example, as described above, the base station may allocate an additional grant such that the UE may perform retransmission for a grant of which transmission is omitted and thereby guarantee URLLC data transmission. Accordingly, the UE may perform retransmission for a grant of which transmission is omitted through the grant allocated from the base station.

[0140] Meanwhile, for example, in association with the aforementioned operation, a case in which a collision occurs between configured grants may be applied as a case in which a plurality of configured grants for different services is configured in the UE. That is, for different services, there is a need to guarantee transmission for a grant of which transmission is omitted in view of URLLC data transmission. Accordingly, as described above, the UE may configure a MAC PDU for a grant of which transmission is omitted and may perform transmission. However, it is provided as an example only.

[0141] In detail, for example, referring to FIG. 8, the UE may perform transmission through configured grant **1** (CG1) and configured grant **2** (CG2). Here, if a collision occurs between a grant **810** for CG1 and a grant **820** for CG2, the UE may configure a MAC PDU for a configured grant having high priority and may perform transmission. For example, in FIG. 8, the UE may perform transmission by selecting the grant **810** for CG1 and by configuring the MAC PDU for the selected grant **810**. Here, the UE may not select the grant **820** for CG2 having low priority and may not configure a MAC PDU for CG2. Next, the UE may configure a MAC PDU for CG2 through an additional grant **830** and may perform transmission. Here, for example, as described above, the UE may expect to perform transmission using the uplink grant **830** addressed to C-RNTI. Here, as described above, the UE may configure a MAC PDU only for LCH and a grant having high priority with respect to the uplink grant **830** addressed to C-RNTI. As another example, to guarantee URLLC data transmission, if an HARQ process ID of the corresponding uplink grant **830** is identical to an HARQ process ID of which transmission is omitted, the UE may configure a MAC PDU for data of which transmission is omitted and may perform transmission through the corresponding uplink grant **830**, which is described above. Here, in FIG. 8, the HARQ process ID of which transmission is omitted may be HARQ process #2 and the HARQ process ID for the uplink grant **830** newly allocated to the UE may also be HARQ process #2. That is, as described above, since the HARQ process ID of the corresponding uplink grant **830** is identical to the HARQ process ID of which transmission is omitted, the UE may perform retransmission for a grant of which is omitted through the corresponding uplink grant **830**.

[0142] FIG. 9 is a flowchart illustrating an operation of a UE according to the present disclosure. For example, in operation **S910**, a plurality of configured grants may be configured in the UE. Here, as described above with reference to FIGS. 1 to 8, in operation **S920**, the UE may verify whether a collision occurs between the configured grants. Here, if the collision occurs between the plurality of configured grants, the UE may perform LCH comparison between the configured grants in operation **S930**. In detail, as described above, the UE may perform an LCP process to verify whether the plurality of configured grants is configured for the same service. Here, if the plurality of configured grants relates to the same LCH in operation **S940**, the UE may verify that the plurality of configured grants is configured for the same service. Here, as described above with reference to FIGS. 1 to 8, in operation **S950**, the UE may select a temporally preceding grant from among the colliding plurality of configured grants and may configure a MAC PDU. Here, as described above, the UE may not configure a MAC PDU for a configured grant of which transmission is omitted. In operation **S960**, the UE may transmit the configured MAC PDU, which is described above. Meanwhile, for example, as described above, unless the collision occurs between the plurality of configured grants, the UE may configure a MAC PDU for a corresponding configured grant in operation **S970** and may transmit the MAC PDU.

[0143] Also, for example, FIG. 10 is a flowchart illustrating a UE operation method in a circumstance in which a collision occurs between a plurality of configured grants according to the present disclosure. For example, in operation **S1010**, a plurality of configured grants may be configured in the UE. Here, as described above with reference to FIGS. 1 to 8, in operation **S1020**, the UE may verify whether a collision occurs between the configured grants. Here, if the collision occurs between the plurality of configured grants, the UE may perform LCH comparison between the configured grants in operation **S1030**. In detail, as described above, the UE may perform an LCP process to verify whether the plurality of configured grants is configured for the same service. Here, if the plurality of configured grants relates to different LCHs in operation **S1040**, the UE may verify that the plurality of configured grants is configured for different services. Here, as described above with reference to FIGS. 1 to 8, the UE may

compare LCH priority between the colliding plurality of grants in operation **S1050**. In operation **S1060**, the UE may select a grant having high LCH priority and may configure a MAC PDU for the selected grant. Next, in operation **S1070**, the UE may transmit the configured MAC PDU. Meanwhile, for example, the UE may configure a MAC PDU for a configured grant of which transmission is omitted. For example, as described above, the UE may expect a retransmission grant by starting “configuredgrantTimer,” without transmitting the configured MAC PDU. Here, the UE may perform transmission for a configured grant of which transmission is omitted through a grant allocated from the base station based on CS-RNTI. Here, as described above, since the MAC PDU is configured, the UE may immediately transmit the MAC PDU for the configured grant of which transmission is omitted, thereby preventing latency. Meanwhile, for example, as described above, unless the collision occurs between the plurality of configured grants, the UE may configure a MAC PDU for a corresponding configured grant in operation **S1080** and may transmit the MAC PDU.

[0144] Also, for example, FIG. **11** is a flowchart illustrating a UE operation method in a circumstance in which a collision occurs between a plurality of configured grants according to the present disclosure. For example, in operation **S1110**, a plurality of configured grants may be configured in the UE. Here, as described above with reference to FIGS. **1** to **8**, in operation **S1120**, the UE may verify whether a collision occurs between the configured grants. Here, if the collision occurs between the plurality of configured grants, the UE may perform LCH comparison between the configured grants in operation **S1130**. In detail, as described above, the UE may perform an LCP process to verify whether the plurality of configured grants is configured for the same service. That is, in operation **S1140**, the UE may verify whether the plurality of configured grants relates to the same LCH. Here, if the plurality of configured grants relates to the same LCH, the UE may select a temporally preceding configured grant and may configure a MAC PDU for the selected configured grant in operation **S1150**. Next, the UE may transmit the configured MAC PDU, which is described above. That is, if the plurality of configured grants is configured for the same service, the UE may configure a MAC PDU for a temporally preceding configured grant and may perform transmission. On the contrary, if a logical channel selected through the LCP process is different for each of the colliding grants in operation **S1180**, the UE may verify that the configured grants relate to different services. Here, in operation **S1180**, the UE may select a single grant to perform transmission through priority comparison between logical channels. For example, in operation **S1180**, the UE may configure a MAC PDU for a grant of which transmission is determined based on priority and may store the configured MAC PDU in a corresponding HARQ process. Also, although the UE may configure a MAC PDU even for a grant of which transmission is omitted based on priority and may store the configured MAC PDU in a corresponding HARQ process, the UE may expect a retransmission grant by starting “configuredgrantTimer” without performing transmission in operation **S1190**, which is described above. Here, if the UE receives an uplink grant addressed to CS-RNTI, the UE may immediately transmit the MAC PDU, thereby meeting requirements for URLLC data that is not transmitted due to priority. Alternatively, the UE may not configure a MAC PDU for a grant of which transmission is omitted based on priority and may perform transmission through an additional uplink grant addressed to C-RNTI in operation **S1190**, which is described above. Here, as described above, to transmit dropped data through a grant, if an HARQ process ID of the corresponding uplink grant is identical to an HARQ process ID of a grant of which transmission is omitted by the UE, the UE may configure and transmit a MAC PDU as data for a corresponding logical channel in view

[0145] of the purpose of transmitting data of which transmission is omitted and that is dropped in operation **S1160**. That is, if the collision occurs between the configured grants configured for different services, the UE may support transmission of all packets, thereby meeting requirements of URLLC data. On the contrary, unless the collision occurs between the configured grants, the UE may configure a MAC PDU for a corresponding grant and may perform transmission in operation **S1170**, which is described above.

[0146] FIG. **12** is a diagram illustrating a device configuration according to the present disclosure.

[0147] A base station device **1200** may include a processor **1220**, an antenna device **1212**, a transceiver **1214**, and a memory **1216**.

[0148] The processor **1220** may perform baseband-related signal processing and may include an upper layer processing **1230** and a physical (PHY) layer processing **1240**. The upper layer processing **1230** may process an operation (e.g., uplink received signal processing and downlink transmission signal processing) of a PHY layer. The processor **1220** may also control the overall operation of the base station device **1200** in addition to performing the baseband-related signal processing.

[0149] The antenna device **1212** may include at least one physical antenna. If the antenna device **1212** includes a plurality of antennas, multiple input multiple output (MIMO) transmission and reception may be supported. The transceiver **1214** may include a radio frequency (RF) transmitter and an RF receiver. The memory **1216** may store operation processed information of the processor **1220**, software, an operating system (OS), an application, etc., associated with an operation of the base station device **1200**, and may include a component such as a buffer.

[0150] The processor **1220** of the base station **1200** may be configured to implement an operation of a base station in the examples described herein.

[0151] The terminal device **1250** may include a processor **1270**, an antenna device **1262**, a transceiver **1264**, and a memory **1266**. Meanwhile, for example, herein, communication between terminal devices may be performed based on uplink/downlink communication. That is, each terminal device **1250** that performs uplink/downlink communication herein may be a device that performs communication with the terminal device **1250** as well as the base station device **1200**.

[0152] However, it is provided as an example only.

[0153] The processor **1270** may perform baseband-related signal processing and may include an upper layer processing **1280** and a PHY layer processing **1290**. The upper layer processing **1280** may process an operation of a MAC layer, an RRC layer, or more upper layers. The PHY layer processing **1290** may process an operation (e.g., downlink received signal processing and uplink transmission signal processing) of a PHY layer. The processor **1270** may control the overall operation of the terminal device **1250** in addition to performing the baseband-related signal processing.

[0154] The antenna device **1262** may include at least one physical antenna. If the antenna device **1262** includes a plurality of antennas, MIMO transmission and reception may be supported. The transceiver **1264** may include an RF transmitter and an RF receiver. The memory **1266** may store operation processed information of the processor **1270** and software, an OS, an application, etc., associated with an operation of the terminal device **1250**, and may include a component, such as a buffer.

[0155] The processor **1270** of the terminal device **1250** may be configured to implement an operation of a terminal in the examples described herein.

[0156] Also, for example, as described above, the processor **1220** of the base station **1200** may configure a configured grant in the terminal device **1250**. Here, as described above, the configured grant may be configured in the terminal based on type 1 or type 2.

[0157] For example, the processor **1220** of the base station **1200** may configure a configured grant of type 1 in the terminal through an RRC message (or an RRC reconfiguration message). Also, the processor **1220** of the base station **1200** may provide parameter information about the configured grant to the terminal. Here, the processor **1270** of the terminal device **1250** may perform data transmission through the configured grant based on the parameter information.

[0158] Also, for example, the processor **1220** of the base station **1200** may dynamically configure a configured grant of type 2 in the terminal through a PDCCH. Here, as described above, the processor **1270** of the terminal device **1250** may perform data transmission through the configured grant.

[0159] Also, for example, as described above, the processor **1270** of the terminal device **1250** may verify whether a collision occurs between a plurality of configured grants. For example, the upper layer processing **1280** of the terminal device **1250** may verify whether the collision occurs between the plurality of configured grants. Here, the processor **1270** of the terminal device **1250** may compare logical channels for the plurality of configured grants. As described above, the processor **1270** of the terminal device **1250** may verify whether the plurality of configured grants relates to the same service. Here, as described above, with respect to the configured grants for the same service, the processor **1270** of the terminal device **1250** may configure a MAC PDU for a temporally preceding configured grant and may perform transmission. Also, for example, as described above, with respect to the configured grants for different services, the processor **1270** of the terminal device **1250** may configure a MAC PDU for a configured grant based on priority and may perform transmission.

[0160] The various examples herein are to explain the representative aspects of the present disclosure instead of describing all the possible combinations and matters described in the various examples may independently apply or may apply through at least two combinations thereof. [0161] Also, various examples of the present disclosure may be implemented by hardware, firmware, software, or combination thereof. In the case of implementation by hardware, the examples may be implemented by one or more application-specific integrated circuits (ASICs), digital signal processors (DSPs), digital signal processing devices (DSPDs), programmable logic devices (PLDs), field programmable gate arrays (FPGAs), general processors, controllers, microcontrollers, microprocessors, etc. [0162] The scope of the present disclosure includes software or machine-executable instructions (e.g., OS, application, firmware, program, etc.) such that operations of the method of the various examples may be executed on an apparatus or a computer, and a non-transitory computer-readable medium storing such software or instructions to be executable on an apparatus or a computer.

Claims

1. A user equipment (UE) comprising: an antenna; a transceiver; a processor; and a memory storing instructions that, when executed by the processor, cause the UE to: receive a plurality of configured grants, wherein the plurality of configured grants comprises a configured grant for at least one service configured in a single bandwidth part (BWP), wherein an overlap occurs between the plurality of configured grants; select a first configured grant from among a plurality of overlapped configured grants, wherein the first configured grant is selected based on a priority for a logical channel corresponding to the first configured grant, wherein the priority is indicated by a radio resource control (RRC) message received from a base station, and wherein a second configured grant of the overlapped configured grants is ignored; transmit, using the first configured grant, traffic associated with the logical channel; receive allocation of a retransmission grant addressed to a configured scheduling radio network temporary identifier (CS-RNTI); and perform retransmission of traffic for a corresponding service by verifying a Hybrid Automatic Repeat Request (HARQ) process identifier (ID) of the retransmission grant.
2. The UE of claim 1, wherein: a first BWP supports a plurality of services comprising a first service, a second service, and a third service; the plurality of configured grants are associated with the plurality of services; and at least one configured grant, of the plurality of configured grants, is configured for each of the plurality of services.
3. The UE of claim 2, wherein: a second BWP supports a fourth service and a fifth service; the plurality of configured grants are associated with the fourth service and the fifth service; and at least one configured grant, of the plurality of configured grants, is configured for each of the fourth service and the fifth service.
4. The UE of claim 2, wherein the instructions, when executed by the processor, cause the UE to: identify a transmission point, in time, of traffic for each of the plurality of services using the configured grants for the plurality of services of the first BWP, respectively; and determine whether transmission points of traffic overlap in time among the plurality of services.
5. The UE of claim 1, wherein the instructions, when executed by the processor, cause the UE to: identify transmission points for transmitting traffic that are overlapped in time.
6. The UE of claim 1, wherein the instructions, when executed by the processor, cause the UE to: receive, from the base station and using the CS-RNTI for retransmission of a second configured grant configured for the UE, an indication of an uplink resource; and transmit, using the uplink resource, traffic for a service corresponding to a dropped configured grant.
7. The UE of claim 1, wherein the first configured grant configures the UE to transmit uplink data without performing a scheduling request (SR) transmission.
8. The UE of claim 1, wherein the instructions, when executed by the processor, cause the UE to: receive, using a cell radio network temporary identifier (C-RNTI), an indication of an uplink resource from the base station; and transmit, using the uplink resource, traffic for a service corresponding to a dropped configured grant.
9. The UE of claim 1, wherein the instructions, when executed by the processor, cause the UE to: activate one of a first BWP or a second BWP that is indicated by a BWP indicator comprised in a Physical Downlink Control Channel (PDCCH) received from the base station; and deactivate the other one of the first BWP or the second BWP that is not indicated by the BWP indicator.
10. A wireless user device comprising: an antenna; a transceiver; a processor; and a memory storing instructions that, when executed by the processor, cause the wireless user device to: receive a plurality of configured grants associated with a bandwidth part (BWP), wherein an overlap occurs between the plurality of configured grants; based on overlapped configured grants of the plurality of configured grants, select a first configured grant from the overlapped configured grants, wherein the first configured grant is selected based on a priority associated with the first configured grant, and wherein the priority is indicated by a radio resource control (RRC) message received from a base station; and based on the first configured grant, transmit an uplink signal associated with the first configured grant; after ignoring a second configured grant of the overlapped configured grants, receive, from the base station and using a configured scheduling radio network temporary identifier (CS-RNTI) for retransmission associated with the ignored second configured grant, an indication of an uplink resource; and transmit, using the uplink resource, an uplink signal associated with the ignored second configured grant.
11. The wireless user device of claim 10, wherein uplink resources, for Hybrid Automatic Repeat Request (HARQ) transmissions or HARQ retransmissions, are allocated via the plurality of configured grants.
12. The wireless user device of claim 10, wherein the instructions, when executed by the processor, cause the wireless user device to verify whether transmission points for transmitting traffic are overlapped in time.
13. The wireless user device of claim 10, wherein the instructions, when executed by the processor, cause the wireless user device to: receive allocation of a retransmission grant addressed to the CS-RNTI; and based on a Hybrid Automatic Repeat Request (HARQ) process identifier (ID) of the retransmission grant, perform retransmission of an uplink signal.
14. The wireless user device of claim 10, wherein the instructions, when executed by the processor, cause the wireless user device to: after ignoring a second configured grant of the overlapped configured grants, receive, using a cell radio network temporary identifier (C-RNTI), an indication of an uplink resource from the base station; and transmit, using the uplink resource, an uplink signal associated with the ignored second configured grant.
15. The wireless user device of claim 10, wherein the first configured grant configures the wireless user device to transmit uplink data without performing a scheduling request (SR) transmission.
16. A user equipment (UE) comprising: an antenna; a transceiver; a processor; and a memory storing instructions that, when executed by the processor, cause the UE to: receive a plurality of uplink grants of a bandwidth part (BWP) of a cell, wherein the plurality of configured grants comprises: a configured grant configured by a radio resource control (RRC) reconfiguration message; and a second uplink grant associated with an indication via a physical downlink control channel (PDCCH); based on a transmission time duration associated with the configured grant overlapping with a transmission time duration associated with the second uplink grant, the configured grant: select the second uplink grant; and ignore the configured grant, wherein ignoring of the configured grant is based on a priority for a logical channel corresponding to the configured grant, and wherein the priority is indicated by a radio resource control (RRC) message received from a base station; and transmit, using the second uplink grant, uplink data; after ignoring the configured grant of the overlapped configured grants, receive, from the base station and using a configured scheduling radio network temporary identifier (CS-RNTI) for retransmission associated with the ignored configured grant, an indication of an uplink resource; and transmit, using the uplink resource, an uplink signal associated with the ignored configured grant.
17. The UE of claim 16, wherein the configured grant configures the UE to transmit uplink data without performing a scheduling request (SR)

transmission.

18. The UE of claim 16, wherein the configured grant is a configured grant of a first type; and wherein the second uplink grant is a configured grant of a second type.

19. The UE of claim 16, wherein the instructions, when executed by the processor, cause the UE to: after ignoring the configured grant, keep data associated with the ignored configured grant; receive an indication of an uplink resource from the base station; and transmit, using the uplink resource, the kept data associated with the ignored configured grant.

20. The UE of claim 19, wherein the indication of the uplink resource is received using the CS-RNTI.
