

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent

12402906

Kind Code

B2

Date of Patent

September 02, 2025

Inventor(s)

Shelton, IV; Frederick E. et al.

Modular battery powered handheld surgical instrument and methods therefor

Abstract

Disclosed is a method of controlling a modular battery powered handheld surgical instrument. The surgical instrument including a battery, a user input sensor, a controller, a radio frequency (RF) drive circuit, an ultrasonic transducer, ultrasonic transducer drive circuit, and an end effector. The end effector including an electrode electrically coupled to RF drive circuit, an ultrasonic blade acoustically coupled to the ultrasonic transducer, and a sensor to measure tissue parameters. The method includes applying an RF current drive signal to the electrode by the RF drive circuit; applying an ultrasonic drive signal to the ultrasonic transducer by the ultrasonic transducer drive circuit to acoustically excite the ultrasonic blade; controlling intensity, wave shape, and/or frequency of the RF current drive signal and the ultrasonic drive signal on a sensed measure of a tissue or user parameter.

Inventors: Shelton, IV; Frederick E. (Hillsboro, OH), Yates; David C. (Morrow, OH), Houser; Kevin L. (Springboro, OH), Messerly; Jeffrey D. (Cincinnati, OH), Harris; Jason L. (Lebanon, OH), Strobl; Geoffrey S. (Williamsburg, OH), Hensel; Adam D. (Gahanna, OH)

Applicant: Cilag GmbH International (Zug, CH)

Family ID: 59313397

Assignee: Cilag GmbH International (Zug, CH)

Appl. No.: 17/032728

Filed: September 25, 2020

Prior Publication Data

Document Identifier

US 20210100579 A1

Publication Date

Apr. 08, 2021

Related U.S. Application Data

continuation parent-doc US 15382515 20161216 US 10842523 child-doc US 17032728
us-provisional-application US 62330669 20160502
us-provisional-application US 62279635 20160115

Publication Classification

Int. Cl.: **A61B17/32** (20060101); **A61B18/12** (20060101); **A61B18/14** (20060101); **H01M6/02** (20060101); **H01M6/50** (20060101); **H01M10/42** (20060101); **H01M10/46** (20060101); **H01M10/48** (20060101); A61B17/00 (20060101); A61B18/00 (20060101); A61B34/00 (20160101); A61B90/00 (20160101); H01M50/209 (20210101); H01M50/213 (20210101); H01M50/247 (20210101)

U.S. Cl.:

CPC **A61B17/320092** (20130101); **A61B17/320068** (20130101); **A61B18/1206** (20130101); **A61B18/1445** (20130101); **A61B18/1447** (20130101); **H01M6/02** (20130101); **H01M6/5044** (20130101); **H01M10/425** (20130101); **H01M10/46** (20130101); **H01M10/48** (20130101); A61B2017/00017 (20130101); A61B2017/00026 (20130101); A61B2017/00039 (20130101); A61B2017/00084 (20130101); A61B2017/00119 (20130101); A61B2017/00123 (20130101); A61B2017/0023 (20130101); A61B2017/003 (20130101); A61B2017/00323 (20130101); A61B2017/00398 (20130101); A61B2017/0046 (20130101); A61B2017/00464 (20130101); A61B2017/00477 (20130101); A61B2017/00734 (20130101); A61B2017/00876 (20130101); A61B2017/320072 (20130101); A61B2017/320073 (20170801); A61B2017/320074 (20170801); A61B2017/320078 (20170801); A61B2017/320094 (20170801); A61B2017/320095 (20170801); A61B2018/00297 (20130101); A61B2018/00601 (20130101); A61B2018/00607 (20130101); A61B2018/0063 (20130101); A61B2018/00684 (20130101); A61B2018/00767 (20130101); A61B2018/00791 (20130101); A61B2018/00827 (20130101); A61B2018/00875 (20130101); A61B2018/00898 (20130101); A61B2018/00904 (20130101); A61B2018/00946 (20130101); A61B2018/00988 (20130101); A61B2018/00994 (20130101); A61B2018/1226 (20130101); A61B2018/1455 (20130101); A61B2034/252 (20160201); A61B2090/061 (20160201); A61B2560/0209 (20130101); A61B2560/0475 (20130101); A61B2562/0219 (20130101); H01M50/209 (20210101); H01M50/213 (20210101); H01M50/247 (20210101); H01M2220/30 (20130101)

Field of Classification Search

CPC: A61B (17/320092); A61B (18/1206); A61B (18/1445); A61B (18/1447); A61B (2017/00017); A61B (2017/00026); A61B (2017/00039); A61B (2017/00084); A61B (2017/00119); A61B (2017/00123); A61B (2017/0023); A61B (2017/003); A61B (2017/00323); A61B (2017/00398); A61B (2017/0046); A61B (2017/00464); A61B (2017/00477); A61B (2017/00734); A61B (2017/00876); A61B (2017/320072); A61B (2017/320073); A61B (2017/320074); A61B (2017/320078); A61B (2017/320094); A61B (2017/320095); A61B (2018/00297); A61B (2018/00601); A61B (2018/00607); A61B (2018/0063); A61B (2018/00684); A61B (2018/00767); A61B (2018/00791); A61B (2018/00827); A61B (2018/00875); A61B (2018/00898); A61B (2018/00904); A61B

(2018/00946); A61B (2018/00988); A61B (2018/00994); A61B (2018/1226); A61B (2018/1455); A61B (2034/252); A61B (2090/061); A61B (2560/0209); A61B (2560/0475); A61B (2562/0219)

USPC: 606/51-52

References Cited

U.S. PATENT DOCUMENTS

Patent No.	Issued Date	Patentee Name	U.S. Cl.	CPC
969528	12/1909	Disbrow	N/A	N/A
1570025	12/1925	Young	N/A	N/A
1813902	12/1930	Bovie	N/A	N/A
2188497	12/1939	Calva	N/A	N/A
2366274	12/1944	Luth et al.	N/A	N/A
2425245	12/1946	Johnson	N/A	N/A
2442966	12/1947	Wallace	N/A	N/A
2458152	12/1948	Eakins	N/A	N/A
2510693	12/1949	Green	N/A	N/A
2597564	12/1951	Bugg	N/A	N/A
2704333	12/1954	Calosi et al.	N/A	N/A
2736960	12/1955	Armstrong	N/A	N/A
2748967	12/1955	Roach	N/A	N/A
2845072	12/1957	Shafer	N/A	N/A
2849788	12/1957	Creek	N/A	N/A
2867039	12/1958	Zach	N/A	N/A
2874470	12/1958	Richards	N/A	N/A
2990616	12/1960	Balamuth et al.	N/A	N/A
RE25033	12/1960	Balamuth et al.	N/A	N/A
3015961	12/1961	Roney	N/A	N/A
3033407	12/1961	Alfons	N/A	N/A
3053124	12/1961	Balamuth et al.	N/A	N/A
3082805	12/1962	Royce	N/A	N/A
3166971	12/1964	Stoecker	N/A	N/A
3322403	12/1966	Murphy	N/A	N/A
3432691	12/1968	Shoh	N/A	N/A
3433226	12/1968	Boyd	N/A	N/A
3489930	12/1969	Shoh	N/A	N/A
3513848	12/1969	Winston et al.	N/A	N/A
3514856	12/1969	Camp et al.	N/A	N/A
3525912	12/1969	Wallin	N/A	N/A
3526219	12/1969	Balamuth	N/A	N/A
3554198	12/1970	Tatoian et al.	N/A	N/A
3580841	12/1970	Cadotte et al.	N/A	N/A
3606682	12/1970	Camp et al.	N/A	N/A
3614484	12/1970	Shoh	N/A	N/A
3616375	12/1970	Inoue	N/A	N/A
3629726	12/1970	Popescu	N/A	N/A
3636943	12/1971	Balamuth	N/A	N/A

3668486	12/1971	Silver	N/A	N/A
3702948	12/1971	Balamuth	N/A	N/A
3703651	12/1971	Blowers	N/A	N/A
3776238	12/1972	Peyman et al.	N/A	N/A
3777760	12/1972	Essner	N/A	N/A
3805787	12/1973	Banko	N/A	N/A
3809977	12/1973	Balamuth et al.	N/A	N/A
3830098	12/1973	Antonevich	N/A	N/A
3854737	12/1973	Gilliam, Sr.	N/A	N/A
3862630	12/1974	Balamuth	N/A	N/A
3875945	12/1974	Friedman	N/A	N/A
3885438	12/1974	Harris, Sr. et al.	N/A	N/A
3900823	12/1974	Sokal et al.	N/A	N/A
3918442	12/1974	Nikolaev et al.	N/A	N/A
3924335	12/1974	Balamuth et al.	N/A	N/A
3946738	12/1975	Newton et al.	N/A	N/A
3955859	12/1975	Stella et al.	N/A	N/A
3956826	12/1975	Perdreux, Jr.	N/A	N/A
3989952	12/1975	Hohmann	N/A	N/A
4005714	12/1976	Hiltebrandt	N/A	N/A
4012647	12/1976	Balamuth et al.	N/A	N/A
4034762	12/1976	Cosens et al.	N/A	N/A
4058126	12/1976	Leveen	N/A	N/A
4074719	12/1977	Semm	N/A	N/A
4156187	12/1978	Murry et al.	N/A	N/A
4167944	12/1978	Banko	N/A	N/A
4188927	12/1979	Harris	N/A	N/A
4200106	12/1979	Douvas et al.	N/A	N/A
4203430	12/1979	Takahashi	N/A	N/A
4203444	12/1979	Bonnell et al.	N/A	N/A
4220154	12/1979	Semm	N/A	N/A
4237441	12/1979	van Konynenburg et al.	N/A	N/A
4244371	12/1980	Farin	N/A	N/A
4281785	12/1980	Brooks	N/A	N/A
4300083	12/1980	Heiges	N/A	N/A
4302728	12/1980	Nakamura	N/A	N/A
4304987	12/1980	van Konynenburg	N/A	N/A
4306570	12/1980	Matthews	N/A	N/A
4314559	12/1981	Allen	N/A	N/A
4353371	12/1981	Cosman	N/A	N/A
4409981	12/1982	Lundberg	N/A	N/A
4445063	12/1983	Smith	N/A	N/A
4461304	12/1983	Kuperstein	N/A	N/A
4463759	12/1983	Garito et al.	N/A	N/A
4491132	12/1984	Aikins	N/A	N/A
4492231	12/1984	Auth	N/A	N/A
4494759	12/1984	Kieffer	N/A	N/A
4504264	12/1984	Kelman	N/A	N/A
4512344	12/1984	Barber	N/A	N/A

4526571	12/1984	Wuchinich	N/A	N/A
4535773	12/1984	Yoon	N/A	N/A
4541638	12/1984	Ogawa et al.	N/A	N/A
4545374	12/1984	Jacobson	N/A	N/A
4545926	12/1984	Fouts, Jr. et al.	N/A	N/A
4549147	12/1984	Kondo	N/A	N/A
4550870	12/1984	Krumme et al.	N/A	N/A
4553544	12/1984	Nomoto et al.	N/A	N/A
4562838	12/1985	Walker	N/A	N/A
4574615	12/1985	Bower et al.	N/A	N/A
4582236	12/1985	Hirose	N/A	N/A
4593691	12/1985	Lindstrom et al.	N/A	N/A
4608981	12/1985	Rothfuss et al.	N/A	N/A
4617927	12/1985	Manes	N/A	N/A
4633119	12/1985	Thompson	N/A	N/A
4633874	12/1986	Chow et al.	N/A	N/A
4634420	12/1986	Spinoso et al.	N/A	N/A
4640279	12/1986	Beard	N/A	N/A
4641053	12/1986	Takeda	N/A	N/A
4646738	12/1986	Trott	N/A	N/A
4646756	12/1986	Watmough et al.	N/A	N/A
4649919	12/1986	Thimsen et al.	N/A	N/A
4662068	12/1986	Polonsky	N/A	N/A
4674502	12/1986	Imonti	N/A	N/A
4694835	12/1986	Strand	N/A	N/A
4708127	12/1986	Abdelghani	N/A	N/A
4712722	12/1986	Hood et al.	N/A	N/A
4735603	12/1987	Goodson et al.	N/A	N/A
4739759	12/1987	Rexroth et al.	N/A	N/A
4761871	12/1987	O'Connor et al.	N/A	N/A
4808154	12/1988	Freeman	N/A	N/A
4819635	12/1988	Shapiro	N/A	N/A
4827911	12/1988	Broadwin et al.	N/A	N/A
4830462	12/1988	Karny et al.	N/A	N/A
4832683	12/1988	Idemoto et al.	N/A	N/A
4836186	12/1988	Scholz	N/A	N/A
4838853	12/1988	Parisi	N/A	N/A
4844064	12/1988	Thimsen et al.	N/A	N/A
4849133	12/1988	Yoshida et al.	N/A	N/A
4850354	12/1988	McGurk-Burleson et al.	N/A	N/A
4852578	12/1988	Companion et al.	N/A	N/A
4860745	12/1988	Farin et al.	N/A	N/A
4862890	12/1988	Stasz et al.	N/A	N/A
4865159	12/1988	Jamison	N/A	N/A
4867157	12/1988	McGurk-Burleson et al.	N/A	N/A
4878493	12/1988	Pasternak et al.	N/A	N/A
4880015	12/1988	Nierman	N/A	N/A
4881550	12/1988	Kothe	N/A	N/A

4896009	12/1989	Pawlowski	N/A	N/A
4903696	12/1989	Stasz et al.	N/A	N/A
4910389	12/1989	Sherman et al.	N/A	N/A
4915643	12/1989	Samejima et al.	N/A	N/A
4920978	12/1989	Colvin	N/A	N/A
4922902	12/1989	Wuchinich et al.	N/A	N/A
4926860	12/1989	Stice et al.	N/A	N/A
4936842	12/1989	D'Amelio et al.	N/A	N/A
4954960	12/1989	Lo et al.	N/A	N/A
4965532	12/1989	Sakurai	N/A	N/A
4979952	12/1989	Kubota et al.	N/A	N/A
4981756	12/1990	Rhandhawa	N/A	N/A
5001649	12/1990	Lo et al.	N/A	N/A
5003693	12/1990	Atkinson et al.	N/A	N/A
5009661	12/1990	Michelson	N/A	N/A
5013956	12/1990	Kurozumi et al.	N/A	N/A
5015227	12/1990	Broadwin et al.	N/A	N/A
5020514	12/1990	Heckele	N/A	N/A
5026370	12/1990	Lottick	N/A	N/A
5026387	12/1990	Thomas	N/A	N/A
5035695	12/1990	Weber, Jr. et al.	N/A	N/A
5042461	12/1990	Inoue et al.	N/A	N/A
5042707	12/1990	Taheri	N/A	N/A
5052145	12/1990	Wang	N/A	N/A
5061269	12/1990	Muller	N/A	N/A
5075839	12/1990	Fisher et al.	N/A	N/A
5084052	12/1991	Jacobs	N/A	N/A
5099840	12/1991	Goble et al.	N/A	N/A
5104025	12/1991	Main et al.	N/A	N/A
5105117	12/1991	Yamaguchi	N/A	N/A
5106538	12/1991	Barma et al.	N/A	N/A
5108383	12/1991	White	N/A	N/A
5109819	12/1991	Custer et al.	N/A	N/A
5112300	12/1991	Ureche	N/A	N/A
5113139	12/1991	Furukawa	N/A	N/A
5123903	12/1991	Quaid et al.	N/A	N/A
5126618	12/1991	Takahashi et al.	N/A	N/A
D327872	12/1991	McMills et al.	N/A	N/A
5152762	12/1991	McElhenney	N/A	N/A
5156633	12/1991	Smith	N/A	N/A
5160334	12/1991	Billings et al.	N/A	N/A
5162044	12/1991	Gahn et al.	N/A	N/A
5163421	12/1991	Bernstein et al.	N/A	N/A
5163537	12/1991	Radev	N/A	N/A
5163945	12/1991	Ortiz et al.	N/A	N/A
5167619	12/1991	Wuchinich	N/A	N/A
5167725	12/1991	Clark et al.	N/A	N/A
5172344	12/1991	Ehrlich	N/A	N/A
5174276	12/1991	Crockard	N/A	N/A
D332660	12/1992	Rawson et al.	N/A	N/A

5176677	12/1992	Wuchinich	N/A	N/A
5176695	12/1992	Dulebohn	N/A	N/A
5184605	12/1992	Grzeszykowski	N/A	N/A
5188102	12/1992	Idemoto et al.	N/A	N/A
D334173	12/1992	Liu et al.	N/A	N/A
5190517	12/1992	Zieve et al.	N/A	N/A
5190518	12/1992	Takasu	N/A	N/A
5190541	12/1992	Abele et al.	N/A	N/A
5196007	12/1992	Ellman et al.	N/A	N/A
5203380	12/1992	Chikama	N/A	N/A
5205459	12/1992	Brinkerhoff et al.	N/A	N/A
5205817	12/1992	Idemoto et al.	N/A	N/A
5209719	12/1992	Baruch et al.	N/A	N/A
5213569	12/1992	Davis	N/A	N/A
5214339	12/1992	Naito	N/A	N/A
5217460	12/1992	Knoepfler	N/A	N/A
5218529	12/1992	Meyer et al.	N/A	N/A
5221282	12/1992	Wuchinich	N/A	N/A
5222937	12/1992	Kagawa	N/A	N/A
5226909	12/1992	Evans et al.	N/A	N/A
5226910	12/1992	Kajiyama et al.	N/A	N/A
5231989	12/1992	Middleman et al.	N/A	N/A
5234428	12/1992	Kaufman	N/A	N/A
5241236	12/1992	Sasaki et al.	N/A	N/A
5241968	12/1992	Slater	N/A	N/A
5242339	12/1992	Thornton	N/A	N/A
5242460	12/1992	Klein et al.	N/A	N/A
5246003	12/1992	DeLonzor	N/A	N/A
5254129	12/1992	Alexander	N/A	N/A
5257988	12/1992	L'Esperance, Jr.	N/A	N/A
5258004	12/1992	Bales et al.	N/A	N/A
5258006	12/1992	Rydell et al.	N/A	N/A
5261922	12/1992	Hood	N/A	N/A
5263957	12/1992	Davison	N/A	N/A
5264925	12/1992	Shipp et al.	N/A	N/A
5269297	12/1992	Weng et al.	N/A	N/A
5275166	12/1993	Vaitekunas et al.	N/A	N/A
5275607	12/1993	Lo et al.	N/A	N/A
5275609	12/1993	Pingleton et al.	N/A	N/A
5282800	12/1993	Foshee et al.	N/A	N/A
5282817	12/1993	Hoogeboom et al.	N/A	N/A
5285795	12/1993	Ryan et al.	N/A	N/A
5285945	12/1993	Brinkerhoff et al.	N/A	N/A
5290286	12/1993	Parins	N/A	N/A
5293863	12/1993	Zhu et al.	N/A	N/A
5300068	12/1993	Rosar et al.	N/A	N/A
5304115	12/1993	Pflueger et al.	N/A	N/A
D347474	12/1993	Olson	N/A	N/A
5307976	12/1993	Olson et al.	N/A	N/A
5309927	12/1993	Welch	N/A	N/A

5312023	12/1993	Green et al.	N/A	N/A
5312425	12/1993	Evans et al.	N/A	N/A
5318525	12/1993	West et al.	N/A	N/A
5318563	12/1993	Malis et al.	N/A	N/A
5318564	12/1993	Eggers	N/A	N/A
5318570	12/1993	Hood et al.	N/A	N/A
5318589	12/1993	Lichtman	N/A	N/A
5322055	12/1993	Davison et al.	N/A	N/A
5324299	12/1993	Davison et al.	N/A	N/A
5326013	12/1993	Green et al.	N/A	N/A
5326342	12/1993	Pflueger et al.	N/A	N/A
5330471	12/1993	Eggers	N/A	N/A
5330502	12/1993	Hassler et al.	N/A	N/A
5334183	12/1993	Wuchinich	N/A	N/A
5339723	12/1993	Huitema	N/A	N/A
5342356	12/1993	Ellman et al.	N/A	N/A
5342359	12/1993	Rydell	N/A	N/A
5344420	12/1993	Hilal et al.	N/A	N/A
5345937	12/1993	Middleman et al.	N/A	N/A
5346502	12/1993	Estabrook et al.	N/A	N/A
5353474	12/1993	Good et al.	N/A	N/A
5357164	12/1993	Imabayashi et al.	N/A	N/A
5357423	12/1993	Weaver et al.	N/A	N/A
5359994	12/1993	Krauter et al.	N/A	N/A
5361583	12/1993	Huitema	N/A	N/A
5366466	12/1993	Christian et al.	N/A	N/A
5368557	12/1993	Nita et al.	N/A	N/A
5370645	12/1993	Klicek et al.	N/A	N/A
5371429	12/1993	Manna	N/A	N/A
5374813	12/1993	Shipp	N/A	N/A
D354564	12/1994	Medema	N/A	N/A
5381067	12/1994	Greenstein et al.	N/A	N/A
5383874	12/1994	Jackson et al.	N/A	N/A
5383917	12/1994	Desai et al.	N/A	N/A
5387207	12/1994	Dyer et al.	N/A	N/A
5387215	12/1994	Fisher	N/A	N/A
5389098	12/1994	Tsuruta et al.	N/A	N/A
5394187	12/1994	Shipp	N/A	N/A
5395033	12/1994	Byrne et al.	N/A	N/A
5395312	12/1994	Desai	N/A	N/A
5395363	12/1994	Billings et al.	N/A	N/A
5395364	12/1994	Anderhub et al.	N/A	N/A
5396266	12/1994	Brimhall	N/A	N/A
5396900	12/1994	Slater et al.	N/A	N/A
5400267	12/1994	Denen et al.	N/A	N/A
5403312	12/1994	Yates et al.	N/A	N/A
5403334	12/1994	Evans et al.	N/A	N/A
5406503	12/1994	Williams, Jr. et al.	N/A	N/A
5408268	12/1994	Shipp	N/A	N/A
D358887	12/1994	Feinberg	N/A	N/A

5411481	12/1994	Allen et al.	N/A	N/A
5417709	12/1994	Slater	N/A	N/A
5419761	12/1994	Narayanan et al.	N/A	N/A
5421829	12/1994	Olichney et al.	N/A	N/A
5423844	12/1994	Miller	N/A	N/A
5428504	12/1994	Bhatla	N/A	N/A
5429131	12/1994	Scheinman et al.	N/A	N/A
5438997	12/1994	Sieben et al.	N/A	N/A
5441499	12/1994	Fritzsche	N/A	N/A
5443463	12/1994	Stern et al.	N/A	N/A
5445638	12/1994	Rydell et al.	N/A	N/A
5445639	12/1994	Kuslich et al.	N/A	N/A
5447509	12/1994	Mills et al.	N/A	N/A
5449370	12/1994	Vaitekunas	N/A	N/A
5451053	12/1994	Garrido	N/A	N/A
5451161	12/1994	Sharp	N/A	N/A
5451220	12/1994	Ciervo	N/A	N/A
5451227	12/1994	Michaelson	N/A	N/A
5456684	12/1994	Schmidt et al.	N/A	N/A
5458598	12/1994	Feinberg et al.	N/A	N/A
5462604	12/1994	Shibano et al.	N/A	N/A
5465895	12/1994	Knodel et al.	N/A	N/A
5471988	12/1994	Fujio et al.	N/A	N/A
5472443	12/1994	Cordis et al.	N/A	N/A
5476479	12/1994	Green et al.	N/A	N/A
5478003	12/1994	Green et al.	N/A	N/A
5480409	12/1995	Riza	N/A	N/A
5483501	12/1995	Park et al.	N/A	N/A
5484436	12/1995	Eggers et al.	N/A	N/A
5486162	12/1995	Brumbach	N/A	N/A
5486189	12/1995	Mudry et al.	N/A	N/A
5490860	12/1995	Middle et al.	N/A	N/A
5496317	12/1995	Goble et al.	N/A	N/A
5499992	12/1995	Meade et al.	N/A	N/A
5500216	12/1995	Julian et al.	N/A	N/A
5501654	12/1995	Failla et al.	N/A	N/A
5504650	12/1995	Katsui et al.	N/A	N/A
5505693	12/1995	Mackool	N/A	N/A
5507297	12/1995	Slater et al.	N/A	N/A
5507738	12/1995	Ciervo	N/A	N/A
5509922	12/1995	Aranyi et al.	N/A	N/A
5511556	12/1995	DeSantis	N/A	N/A
5520704	12/1995	Castro et al.	N/A	N/A
5522832	12/1995	Kugo et al.	N/A	N/A
5522839	12/1995	Pilling	N/A	N/A
5527331	12/1995	Kresch et al.	N/A	N/A
5531744	12/1995	Nardella et al.	N/A	N/A
5536267	12/1995	Edwards et al.	N/A	N/A
5540681	12/1995	Strul et al.	N/A	N/A
5540684	12/1995	Hassler, Jr.	N/A	N/A

5540693	12/1995	Fisher	N/A	N/A
5542916	12/1995	Hirsch et al.	N/A	N/A
5548286	12/1995	Craven	N/A	N/A
5549637	12/1995	Crainich	N/A	N/A
5553675	12/1995	Pitzen et al.	N/A	N/A
5558671	12/1995	Yates	N/A	N/A
5562609	12/1995	Brumbach	N/A	N/A
5562610	12/1995	Brumbach	N/A	N/A
5562659	12/1995	Morris	N/A	N/A
5562703	12/1995	Desai	N/A	N/A
5563179	12/1995	Stone et al.	N/A	N/A
5569164	12/1995	Lurz	N/A	N/A
5571121	12/1995	Heifetz	N/A	N/A
5573424	12/1995	Poppe	N/A	N/A
5573533	12/1995	Strul	N/A	N/A
5573534	12/1995	Stone	N/A	N/A
5577654	12/1995	Bishop	N/A	N/A
5582609	12/1995	Swanson	607/101	A61N 1/403
5584830	12/1995	Ladd et al.	N/A	N/A
5591187	12/1996	Dekel	N/A	N/A
5593414	12/1996	Shipp et al.	N/A	N/A
5599350	12/1996	Schulze et al.	N/A	N/A
5600526	12/1996	Russell et al.	N/A	N/A
5601601	12/1996	Tal et al.	N/A	N/A
5603773	12/1996	Campbell	N/A	N/A
5607436	12/1996	Pratt et al.	N/A	N/A
5607450	12/1996	Zvenyatsky et al.	N/A	N/A
5609573	12/1996	Sandock	N/A	N/A
5611813	12/1996	Lichtman	N/A	N/A
5618304	12/1996	Hart et al.	N/A	N/A
5618307	12/1996	Donlon et al.	N/A	N/A
5618492	12/1996	Auten et al.	N/A	N/A
5620447	12/1996	Smith et al.	N/A	N/A
5624452	12/1996	Yates	N/A	N/A
5626587	12/1996	Bishop et al.	N/A	N/A
5626595	12/1996	Sklar et al.	N/A	N/A
5626608	12/1996	Cuny et al.	N/A	N/A
5628760	12/1996	Knoepfler	N/A	N/A
5630420	12/1996	Vaitekunas	N/A	N/A
5632432	12/1996	Schulze et al.	N/A	N/A
5632717	12/1996	Yoon	N/A	N/A
5638827	12/1996	Palmer et al.	N/A	N/A
5640741	12/1996	Yano	N/A	N/A
D381077	12/1996	Hunt	N/A	N/A
5647871	12/1996	Levine et al.	N/A	N/A
5649937	12/1996	Bito et al.	N/A	N/A
5649955	12/1996	Hashimoto et al.	N/A	N/A
5651780	12/1996	Jackson et al.	N/A	N/A
5653713	12/1996	Michelson	N/A	N/A
5655100	12/1996	Ebrahim et al.	N/A	N/A

5658281	12/1996	Heard	N/A	N/A
5662662	12/1996	Bishop et al.	N/A	N/A
5662667	12/1996	Knodel	N/A	N/A
5665085	12/1996	Nardella	N/A	N/A
5665100	12/1996	Yoon	N/A	N/A
5669922	12/1996	Hood	N/A	N/A
5674219	12/1996	Monson et al.	N/A	N/A
5674220	12/1996	Fox et al.	N/A	N/A
5674235	12/1996	Parisi	N/A	N/A
5678568	12/1996	Uchikubo et al.	N/A	N/A
5688270	12/1996	Yates et al.	N/A	N/A
5690269	12/1996	Bolanos et al.	N/A	N/A
5693042	12/1996	Boiarski et al.	N/A	N/A
5693051	12/1996	Schulze et al.	N/A	N/A
5694936	12/1996	Fujimoto et al.	N/A	N/A
5695510	12/1996	Hood	N/A	N/A
5700261	12/1996	Brinkerhoff	N/A	N/A
5704534	12/1997	Huitema et al.	N/A	N/A
5704791	12/1997	Gillio	N/A	N/A
5707369	12/1997	Vaitekunas et al.	N/A	N/A
5709680	12/1997	Yates et al.	N/A	N/A
5711472	12/1997	Bryan	N/A	N/A
5713896	12/1997	Nardella	N/A	N/A
5715817	12/1997	Stevens-Wright et al.	N/A	N/A
5716366	12/1997	Yates	N/A	N/A
5717306	12/1997	Shipp	N/A	N/A
5720742	12/1997	Zacharias	N/A	N/A
5720744	12/1997	Eggleston et al.	N/A	N/A
5722980	12/1997	Schulz et al.	N/A	N/A
5723970	12/1997	Bell	N/A	N/A
5728130	12/1997	Ishikawa et al.	N/A	N/A
5730752	12/1997	Alden et al.	N/A	N/A
5733074	12/1997	Stock et al.	N/A	N/A
5735848	12/1997	Yates et al.	N/A	N/A
5741226	12/1997	Strukel et al.	N/A	N/A
5743906	12/1997	Parins et al.	N/A	N/A
5752973	12/1997	Kieturakis	N/A	N/A
5755717	12/1997	Yates et al.	N/A	N/A
5759183	12/1997	VanDusseldorp	N/A	N/A
5762255	12/1997	Chrisman et al.	N/A	N/A
5766164	12/1997	Mueller et al.	N/A	N/A
5772659	12/1997	Becker et al.	N/A	N/A
5776130	12/1997	Buyse et al.	N/A	N/A
5776155	12/1997	Beaupre et al.	N/A	N/A
5779130	12/1997	Alesi et al.	N/A	N/A
5779701	12/1997	McBrayer et al.	N/A	N/A
5782834	12/1997	Lucey et al.	N/A	N/A
5792135	12/1997	Madhani et al.	N/A	N/A
5792138	12/1997	Shipp	N/A	N/A

5792165	12/1997	Klieman et al.	N/A	N/A
5796188	12/1997	Bays	N/A	N/A
5797941	12/1997	Schulze et al.	N/A	N/A
5797958	12/1997	Yoon	N/A	N/A
5797959	12/1997	Castro et al.	N/A	N/A
5800432	12/1997	Swanson	N/A	N/A
5800448	12/1997	Banko	N/A	N/A
5800449	12/1997	Wales	N/A	N/A
5805140	12/1997	Rosenberg et al.	N/A	N/A
5807393	12/1997	Williamson, IV et al.	N/A	N/A
5808396	12/1997	Boukhny	N/A	N/A
5810811	12/1997	Yates et al.	N/A	N/A
5810828	12/1997	Lightman et al.	N/A	N/A
5810859	12/1997	DiMatteo et al.	N/A	N/A
5817033	12/1997	DeSantis et al.	N/A	N/A
5817084	12/1997	Jensen	N/A	N/A
5817093	12/1997	Williamson, IV et al.	N/A	N/A
5817119	12/1997	Klieman et al.	N/A	N/A
5823197	12/1997	Edwards	N/A	N/A
5827271	12/1997	Buysse et al.	N/A	N/A
5827323	12/1997	Klieman et al.	N/A	N/A
5828160	12/1997	Sugishita	N/A	N/A
5833696	12/1997	Whitfield et al.	N/A	N/A
5836897	12/1997	Sakurai et al.	N/A	N/A
5836909	12/1997	Cosmescu	N/A	N/A
5836943	12/1997	Miller, III	N/A	N/A
5836957	12/1997	Schulz et al.	N/A	N/A
5836990	12/1997	Li	N/A	N/A
5843109	12/1997	Mehta et al.	N/A	N/A
5851212	12/1997	Zirps et al.	N/A	N/A
5853412	12/1997	Mayenberger	N/A	N/A
5854590	12/1997	Dalstein	N/A	N/A
5858018	12/1998	Shipp et al.	N/A	N/A
5865361	12/1998	Milliman et al.	N/A	N/A
5873873	12/1998	Smith et al.	N/A	N/A
5873882	12/1998	Straub et al.	N/A	N/A
5876401	12/1998	Schulze et al.	N/A	N/A
5878193	12/1998	Wang et al.	N/A	N/A
5879364	12/1998	Bromfield et al.	N/A	N/A
5880668	12/1998	Hall	N/A	N/A
5883615	12/1998	Fago et al.	N/A	N/A
5891142	12/1998	Eggers et al.	N/A	N/A
5893835	12/1998	Witt et al.	N/A	N/A
5897523	12/1998	Wright et al.	N/A	N/A
5897569	12/1998	Kellogg et al.	N/A	N/A
5903607	12/1998	Tailliet	N/A	N/A
5904681	12/1998	West, Jr.	N/A	N/A
5906625	12/1998	Bito et al.	N/A	N/A

5906627	12/1998	Spaulding	N/A	N/A
5906628	12/1998	Miyawaki et al.	N/A	N/A
5910129	12/1998	Koblish et al.	N/A	N/A
5911699	12/1998	Anis et al.	N/A	N/A
5913823	12/1998	Hedberg et al.	N/A	N/A
5916229	12/1998	Evans	N/A	N/A
5921956	12/1998	Grinberg et al.	N/A	N/A
5929846	12/1998	Rosenberg et al.	N/A	N/A
5935143	12/1998	Hood	N/A	N/A
5935144	12/1998	Estabrook	N/A	N/A
5938633	12/1998	Beaupre	N/A	N/A
5944718	12/1998	Austin et al.	N/A	N/A
5944737	12/1998	Tsonton et al.	N/A	N/A
5947984	12/1998	Whipple	N/A	N/A
5954717	12/1998	Behl et al.	N/A	N/A
5954736	12/1998	Bishop et al.	N/A	N/A
5954746	12/1998	Holthaus et al.	N/A	N/A
5957882	12/1998	Nita et al.	N/A	N/A
5957943	12/1998	Vaitekunas	N/A	N/A
5968007	12/1998	Simon et al.	N/A	N/A
5968060	12/1998	Kellogg	N/A	N/A
5974342	12/1998	Petrofsky	N/A	N/A
D416089	12/1998	Barton et al.	N/A	N/A
5980510	12/1998	Tsonton et al.	N/A	N/A
5980546	12/1998	Hood	N/A	N/A
5984938	12/1998	Yoon	N/A	N/A
5987344	12/1998	West	N/A	N/A
5989274	12/1998	Davison et al.	N/A	N/A
5989275	12/1998	Estabrook et al.	N/A	N/A
5993465	12/1998	Shipp et al.	N/A	N/A
5993972	12/1998	Reich et al.	N/A	N/A
5994855	12/1998	Lundell et al.	N/A	N/A
6003517	12/1998	Sheffield et al.	N/A	N/A
6004335	12/1998	Vaitekunas et al.	N/A	N/A
6011416	12/1999	Mizuno et al.	N/A	N/A
6013052	12/1999	Durman et al.	N/A	N/A
6024741	12/1999	Williamson, IV et al.	N/A	N/A
6024744	12/1999	Kese et al.	N/A	N/A
6024750	12/1999	Mastri et al.	N/A	N/A
6027515	12/1999	Cimino	N/A	N/A
6031526	12/1999	Shipp	N/A	N/A
6033375	12/1999	Brumbach	N/A	N/A
6033399	12/1999	Gines	N/A	N/A
6036667	12/1999	Manna et al.	N/A	N/A
6036707	12/1999	Spaulding	N/A	N/A
6039734	12/1999	Goble	N/A	N/A
6048224	12/1999	Kay	N/A	N/A
6050943	12/1999	Slayton et al.	N/A	N/A
6050996	12/1999	Schmaltz et al.	N/A	N/A

6051010	12/1999	DiMatteo et al.	N/A	N/A
6056735	12/1999	Okada et al.	N/A	N/A
6063098	12/1999	Houser et al.	N/A	N/A
6066132	12/1999	Chen et al.	N/A	N/A
6066151	12/1999	Miyawaki et al.	N/A	N/A
6068627	12/1999	Orszulak et al.	N/A	N/A
6068629	12/1999	Haissaguerre et al.	N/A	N/A
6068647	12/1999	Witt et al.	N/A	N/A
6074389	12/1999	Levine et al.	N/A	N/A
6077285	12/1999	Boukhny	N/A	N/A
6080149	12/1999	Huang et al.	N/A	N/A
6083191	12/1999	Rose	N/A	N/A
6086584	12/1999	Miller	N/A	N/A
6090120	12/1999	Wright et al.	N/A	N/A
6091995	12/1999	Ingle et al.	N/A	N/A
6096033	12/1999	Tu et al.	N/A	N/A
6099483	12/1999	Palmer et al.	N/A	N/A
6099542	12/1999	Cohn et al.	N/A	N/A
6099550	12/1999	Yoon	N/A	N/A
6102909	12/1999	Chen et al.	N/A	N/A
6109500	12/1999	Alli et al.	N/A	N/A
6110127	12/1999	Suzuki	N/A	N/A
6113594	12/1999	Savage	N/A	N/A
6113598	12/1999	Baker	N/A	N/A
6117152	12/1999	Huitema	N/A	N/A
H1904	12/1999	Yates et al.	N/A	N/A
6126629	12/1999	Perkins	N/A	N/A
6126658	12/1999	Baker	N/A	N/A
6129735	12/1999	Okada et al.	N/A	N/A
6129740	12/1999	Michelson	N/A	N/A
6132368	12/1999	Cooper	N/A	N/A
6132427	12/1999	Jones et al.	N/A	N/A
6132429	12/1999	Baker	N/A	N/A
6132448	12/1999	Perez et al.	N/A	N/A
6139320	12/1999	Hahn	N/A	N/A
6139561	12/1999	Shibata et al.	N/A	N/A
6142615	12/1999	Qiu et al.	N/A	N/A
6142994	12/1999	Swanson et al.	N/A	N/A
6144402	12/1999	Norsworthy et al.	N/A	N/A
6147560	12/1999	Erhage et al.	N/A	N/A
6152902	12/1999	Christian et al.	N/A	N/A
6152923	12/1999	Ryan	N/A	N/A
6154198	12/1999	Rosenberg	N/A	N/A
6156029	12/1999	Mueller	N/A	N/A
6159160	12/1999	Hsei et al.	N/A	N/A
6159175	12/1999	Strukel et al.	N/A	N/A
6162194	12/1999	Shipp	N/A	N/A
6162208	12/1999	Hipps	N/A	N/A
6165150	12/1999	Banko	N/A	N/A
6174309	12/2000	Wrublewski et al.	N/A	N/A

6174310	12/2000	Kirwan, Jr.	N/A	N/A
6176857	12/2000	Ashley	N/A	N/A
6179853	12/2000	Sachse et al.	N/A	N/A
6183426	12/2000	Akisada et al.	N/A	N/A
6187003	12/2000	Buysse et al.	N/A	N/A
6190386	12/2000	Rydell	N/A	N/A
6193709	12/2000	Miyawaki et al.	N/A	N/A
6204592	12/2000	Hur	N/A	N/A
6205383	12/2000	Hermann	N/A	N/A
6205855	12/2000	Pfeiffer	N/A	N/A
6206844	12/2000	Reichel et al.	N/A	N/A
6206876	12/2000	Levine et al.	N/A	N/A
6210337	12/2000	Dunham et al.	N/A	N/A
6210402	12/2000	Olsen et al.	N/A	N/A
6210403	12/2000	Klicek	N/A	N/A
6214023	12/2000	Whipple et al.	N/A	N/A
6228080	12/2000	Gines	N/A	N/A
6231565	12/2000	Tovey et al.	N/A	N/A
6232899	12/2000	Craven	N/A	N/A
6233476	12/2000	Strommer et al.	N/A	N/A
6238366	12/2000	Savage et al.	N/A	N/A
6238384	12/2000	Peer	N/A	N/A
6241724	12/2000	Fleischman et al.	N/A	N/A
6245065	12/2000	Panescu et al.	N/A	N/A
6251110	12/2000	Wampler	N/A	N/A
6252110	12/2000	Uemura et al.	N/A	N/A
D444365	12/2000	Bass et al.	N/A	N/A
D445092	12/2000	Lee	N/A	N/A
D445764	12/2000	Lee	N/A	N/A
6254623	12/2000	Haibel, Jr. et al.	N/A	N/A
6257241	12/2000	Wampler	N/A	N/A
6258034	12/2000	Hanafy	N/A	N/A
6259230	12/2000	Chou	N/A	N/A
6261286	12/2000	Goble et al.	N/A	N/A
6267761	12/2000	Ryan	N/A	N/A
6270831	12/2000	Kumar et al.	N/A	N/A
6273852	12/2000	Lehe et al.	N/A	N/A
6274963	12/2000	Estabrook et al.	N/A	N/A
6277115	12/2000	Saadat	N/A	N/A
6277117	12/2000	Tetzlaff et al.	N/A	N/A
6278218	12/2000	Madan et al.	N/A	N/A
6280407	12/2000	Manna et al.	N/A	N/A
6283981	12/2000	Beaupre	N/A	N/A
6287344	12/2000	Wampler et al.	N/A	N/A
6290575	12/2000	Shipp	N/A	N/A
6292700	12/2000	Morrison et al.	N/A	N/A
6299591	12/2000	Banko	N/A	N/A
6306131	12/2000	Hareyama et al.	N/A	N/A
6306157	12/2000	Shchervinsky	N/A	N/A
6309400	12/2000	Beaupre	N/A	N/A

6311783	12/2000	Harpell	N/A	N/A
6319221	12/2000	Savage et al.	N/A	N/A
6325795	12/2000	Lindemann et al.	N/A	N/A
6325799	12/2000	Goble	N/A	N/A
6325811	12/2000	Messerly	N/A	N/A
6328751	12/2000	Beaupre	N/A	N/A
6332891	12/2000	Himes	N/A	N/A
6338657	12/2001	Harper et al.	N/A	N/A
6340352	12/2001	Okada et al.	N/A	N/A
6340878	12/2001	Oglesbee	N/A	N/A
6350269	12/2001	Shipp et al.	N/A	N/A
6352532	12/2001	Kramer et al.	N/A	N/A
6356224	12/2001	Wohlfarth	N/A	N/A
6358246	12/2001	Behl et al.	N/A	N/A
6358264	12/2001	Banko	N/A	N/A
6364888	12/2001	Niemeyer et al.	N/A	N/A
6379320	12/2001	Lafon et al.	N/A	N/A
D457958	12/2001	Dycus et al.	N/A	N/A
6383194	12/2001	Pothula	N/A	N/A
6384690	12/2001	Wilhelmsson et al.	N/A	N/A
6387094	12/2001	Eitenmuller	N/A	N/A
6387109	12/2001	Davison et al.	N/A	N/A
6388657	12/2001	Natoli	N/A	N/A
6390973	12/2001	Ouchi	N/A	N/A
6391026	12/2001	Hung et al.	N/A	N/A
6391042	12/2001	Cimino	N/A	N/A
6398779	12/2001	Buysse et al.	N/A	N/A
6402743	12/2001	Orszulak et al.	N/A	N/A
6402748	12/2001	Schoenman et al.	N/A	N/A
6405184	12/2001	Bohme et al.	N/A	N/A
6405733	12/2001	Fogarty et al.	N/A	N/A
6409722	12/2001	Hoey et al.	N/A	N/A
H2037	12/2001	Yates et al.	N/A	N/A
6416469	12/2001	Phung et al.	N/A	N/A
6416486	12/2001	Wampler	N/A	N/A
6417969	12/2001	DeLuca et al.	N/A	N/A
6419675	12/2001	Gallo, Sr.	N/A	N/A
6423073	12/2001	Bowman	N/A	N/A
6423082	12/2001	Houser et al.	N/A	N/A
6425906	12/2001	Young et al.	N/A	N/A
6428538	12/2001	Blewett et al.	N/A	N/A
6428539	12/2001	Baxter et al.	N/A	N/A
6430446	12/2001	Knowlton	N/A	N/A
6432118	12/2001	Messerly	N/A	N/A
6436114	12/2001	Novak et al.	N/A	N/A
6436115	12/2001	Beaupre	N/A	N/A
6436129	12/2001	Sharkey et al.	N/A	N/A
6440062	12/2001	Ouchi	N/A	N/A
6443968	12/2001	Holthaus et al.	N/A	N/A
6443969	12/2001	Novak et al.	N/A	N/A

6449006	12/2001	Shipp	N/A	N/A
6454781	12/2001	Witt et al.	N/A	N/A
6454782	12/2001	Schwemberger	N/A	N/A
6458128	12/2001	Schulze	N/A	N/A
6458130	12/2001	Frazier et al.	N/A	N/A
6458142	12/2001	Faller et al.	N/A	N/A
6459363	12/2001	Walker et al.	N/A	N/A
6461363	12/2001	Gadberry et al.	N/A	N/A
6464689	12/2001	Qin et al.	N/A	N/A
6464702	12/2001	Schulze et al.	N/A	N/A
6468270	12/2001	Hovda et al.	N/A	N/A
6475211	12/2001	Chess et al.	N/A	N/A
6475215	12/2001	Tanrisever	N/A	N/A
6480796	12/2001	Wiener	N/A	N/A
6485490	12/2001	Wampler et al.	N/A	N/A
6491690	12/2001	Goble et al.	N/A	N/A
6491701	12/2001	Tierney et al.	N/A	N/A
6491708	12/2001	Madan et al.	N/A	N/A
6497715	12/2001	Satou	N/A	N/A
6500112	12/2001	Khoury	N/A	N/A
6500176	12/2001	Truckai et al.	N/A	N/A
6500188	12/2001	Harper et al.	N/A	N/A
6500312	12/2001	Wedekamp	N/A	N/A
6503248	12/2002	Levine	N/A	N/A
6506208	12/2002	Hunt et al.	N/A	N/A
6511478	12/2002	Burnside et al.	N/A	N/A
6511480	12/2002	Tetzlaff et al.	N/A	N/A
6511493	12/2002	Moutafis et al.	N/A	N/A
6514252	12/2002	Nezhat et al.	N/A	N/A
6514267	12/2002	Jewett	N/A	N/A
6517565	12/2002	Whitman et al.	N/A	N/A
6524251	12/2002	Rabiner et al.	N/A	N/A
6524316	12/2002	Nicholson et al.	N/A	N/A
6527736	12/2002	Attinger et al.	N/A	N/A
6531846	12/2002	Smith	N/A	N/A
6533784	12/2002	Truckai et al.	N/A	N/A
6537272	12/2002	Christopherson et al.	N/A	N/A
6537291	12/2002	Friedman et al.	N/A	N/A
6543452	12/2002	Lavigne	N/A	N/A
6543456	12/2002	Freeman	N/A	N/A
6544260	12/2002	Markel et al.	N/A	N/A
6551309	12/2002	LePivert	N/A	N/A
6554829	12/2002	Schulze et al.	N/A	N/A
6558376	12/2002	Bishop	N/A	N/A
6558380	12/2002	Lingenfelder et al.	N/A	N/A
6561983	12/2002	Cronin et al.	N/A	N/A
6562035	12/2002	Levin	N/A	N/A
6562037	12/2002	Paton et al.	N/A	N/A
6565558	12/2002	Lindenmeier et al.	N/A	N/A

6572563	12/2002	Ouchi	N/A	N/A
6572632	12/2002	Zisterer et al.	N/A	N/A
6572639	12/2002	Ingle et al.	N/A	N/A
6575969	12/2002	Rittman, III et al.	N/A	N/A
6582427	12/2002	Goble et al.	N/A	N/A
6582451	12/2002	Marucci et al.	N/A	N/A
6584360	12/2002	Francischelli et al.	N/A	N/A
D477408	12/2002	Bromley	N/A	N/A
6585735	12/2002	Frazier et al.	N/A	N/A
6588277	12/2002	Giordano et al.	N/A	N/A
6589200	12/2002	Schwemberger et al.	N/A	N/A
6589239	12/2002	Khandkar et al.	N/A	N/A
6590733	12/2002	Wilson et al.	N/A	N/A
6599288	12/2002	Maguire et al.	N/A	N/A
6602252	12/2002	Mollenauer	N/A	N/A
6602262	12/2002	Griego et al.	N/A	N/A
6607540	12/2002	Shipp	N/A	N/A
6610059	12/2002	West, Jr.	N/A	N/A
6610060	12/2002	Mulier et al.	N/A	N/A
6611793	12/2002	Burnside et al.	N/A	N/A
6616450	12/2002	Mossle et al.	N/A	N/A
6619529	12/2002	Green et al.	N/A	N/A
6620161	12/2002	Schulze et al.	N/A	N/A
6622731	12/2002	Daniel et al.	N/A	N/A
6623482	12/2002	Pendekanti et al.	N/A	N/A
6623500	12/2002	Cook et al.	N/A	N/A
6623501	12/2002	Heller et al.	N/A	N/A
6626848	12/2002	Neuenfeldt	N/A	N/A
6626926	12/2002	Friedman et al.	N/A	N/A
6629974	12/2002	Penny et al.	N/A	N/A
6632221	12/2002	Edwards et al.	N/A	N/A
6633234	12/2002	Wiener et al.	N/A	N/A
6635057	12/2002	Harano et al.	N/A	N/A
6644532	12/2002	Green et al.	N/A	N/A
6651669	12/2002	Burnside	N/A	N/A
6652513	12/2002	Panescu et al.	N/A	N/A
6652539	12/2002	Shipp et al.	N/A	N/A
6652545	12/2002	Shipp et al.	N/A	N/A
6656132	12/2002	Ouchi	N/A	N/A
6656177	12/2002	Truckai et al.	N/A	N/A
6656198	12/2002	Tsonton et al.	N/A	N/A
6660017	12/2002	Beaupre	N/A	N/A
6662127	12/2002	Wiener et al.	N/A	N/A
6663941	12/2002	Brown et al.	N/A	N/A
6666860	12/2002	Takahashi	N/A	N/A
6666875	12/2002	Sakurai et al.	N/A	N/A
6669690	12/2002	Okada et al.	N/A	N/A
6669710	12/2002	Moutafis et al.	N/A	N/A
6673248	12/2003	Chowdhury	N/A	N/A

6676660	12/2003	Wampler et al.	N/A	N/A
6678621	12/2003	Wiener et al.	N/A	N/A
6679875	12/2003	Honda et al.	N/A	N/A
6679882	12/2003	Kornerup	N/A	N/A
6679899	12/2003	Wiener et al.	N/A	N/A
6682501	12/2003	Nelson et al.	N/A	N/A
6682544	12/2003	Mastri et al.	N/A	N/A
6685700	12/2003	Behl et al.	N/A	N/A
6685701	12/2003	Orszulak et al.	N/A	N/A
6685703	12/2003	Pearson et al.	N/A	N/A
6689145	12/2003	Lee et al.	N/A	N/A
6689146	12/2003	Himes	N/A	N/A
6690960	12/2003	Chen et al.	N/A	N/A
6695840	12/2003	Schulze	N/A	N/A
6702821	12/2003	Bonutti	N/A	N/A
6716215	12/2003	David et al.	N/A	N/A
6719692	12/2003	Kleffner et al.	N/A	N/A
6719765	12/2003	Bonutti	N/A	N/A
6719776	12/2003	Baxter et al.	N/A	N/A
6722552	12/2003	Fenton, Jr.	N/A	N/A
6723091	12/2003	Goble et al.	N/A	N/A
D490059	12/2003	Conway et al.	N/A	N/A
6730080	12/2003	Harano et al.	N/A	N/A
6731047	12/2003	Kauf et al.	N/A	N/A
6733498	12/2003	Paton et al.	N/A	N/A
6733506	12/2003	McDevitt et al.	N/A	N/A
6736813	12/2003	Yamauchi et al.	N/A	N/A
6739872	12/2003	Turri	N/A	N/A
6740079	12/2003	Eggers et al.	N/A	N/A
D491666	12/2003	Kimmell et al.	N/A	N/A
6743245	12/2003	Lobdell	N/A	N/A
6746284	12/2003	Spink, Jr.	N/A	N/A
6746443	12/2003	Morley et al.	N/A	N/A
6752815	12/2003	Beaupre	N/A	N/A
6755825	12/2003	Shoenman et al.	N/A	N/A
6761698	12/2003	Shibata et al.	N/A	N/A
6762535	12/2003	Take et al.	N/A	N/A
6766202	12/2003	Underwood et al.	N/A	N/A
6770072	12/2003	Truckai et al.	N/A	N/A
6773409	12/2003	Truckai	606/49	A61B 18/1815
6773434	12/2003	Ciarrocca	N/A	N/A
6773435	12/2003	Schulze et al.	N/A	N/A
6773443	12/2003	Truwit et al.	N/A	N/A
6773444	12/2003	Messerly	N/A	N/A
6775575	12/2003	Bommannan et al.	N/A	N/A
6778023	12/2003	Christensen	N/A	N/A
6783524	12/2003	Anderson et al.	N/A	N/A
6786382	12/2003	Hoffman	N/A	N/A
6786383	12/2003	Stegelmann	N/A	N/A

6789939	12/2003	Schrodinger et al.	N/A	N/A
6790173	12/2003	Saadat et al.	N/A	N/A
6790216	12/2003	Ishikawa	N/A	N/A
6794027	12/2003	Araki et al.	N/A	N/A
6796981	12/2003	Wham et al.	N/A	N/A
D496997	12/2003	Dycus et al.	N/A	N/A
6800085	12/2003	Selmon et al.	N/A	N/A
6802843	12/2003	Truckai et al.	N/A	N/A
6808525	12/2003	Latterell et al.	N/A	N/A
6809508	12/2003	Donofrio	N/A	N/A
6810281	12/2003	Brock et al.	N/A	N/A
6811842	12/2003	Ehrnsperger et al.	N/A	N/A
6814731	12/2003	Swanson	N/A	N/A
6819027	12/2003	Saraf	N/A	N/A
6821273	12/2003	Mollenauer	N/A	N/A
6827712	12/2003	Tovey et al.	N/A	N/A
6828712	12/2003	Battaglin et al.	N/A	N/A
6835082	12/2003	Gonnering	N/A	N/A
6835199	12/2003	McGuckin, Jr. et al.	N/A	N/A
6840938	12/2004	Morley et al.	N/A	N/A
6843789	12/2004	Goble	N/A	N/A
6849073	12/2004	Hoey et al.	N/A	N/A
6860878	12/2004	Brock	N/A	N/A
6860880	12/2004	Treat et al.	N/A	N/A
6863676	12/2004	Lee et al.	N/A	N/A
6866671	12/2004	Tierney et al.	N/A	N/A
6869439	12/2004	White et al.	N/A	N/A
6875220	12/2004	Du et al.	N/A	N/A
6877647	12/2004	Green et al.	N/A	N/A
6882439	12/2004	Ishijima	N/A	N/A
6887209	12/2004	Kadziauskas et al.	N/A	N/A
6887252	12/2004	Okada et al.	N/A	N/A
6893435	12/2004	Goble	N/A	N/A
6898536	12/2004	Wiener et al.	N/A	N/A
6899685	12/2004	Kermode et al.	N/A	N/A
6905497	12/2004	Truckai et al.	N/A	N/A
6908463	12/2004	Treat et al.	N/A	N/A
6908472	12/2004	Wiener et al.	N/A	N/A
6913579	12/2004	Truckai et al.	N/A	N/A
6915623	12/2004	Dey et al.	N/A	N/A
6923804	12/2004	Eggers et al.	N/A	N/A
6923806	12/2004	Hooven et al.	N/A	N/A
6926712	12/2004	Phan	N/A	N/A
6926716	12/2004	Baker et al.	N/A	N/A
6926717	12/2004	Garito et al.	N/A	N/A
6929602	12/2004	Hirakui et al.	N/A	N/A
6929622	12/2004	Chian	N/A	N/A
6929632	12/2004	Nita et al.	N/A	N/A
6929644	12/2004	Truckai et al.	N/A	N/A
6933656	12/2004	Matsushita et al.	N/A	N/A

D509589	12/2004	Wells	N/A	N/A
6942660	12/2004	Pantera et al.	N/A	N/A
6942677	12/2004	Nita et al.	N/A	N/A
6945981	12/2004	Donofrio et al.	N/A	N/A
6946779	12/2004	Birgel	N/A	N/A
6948503	12/2004	Refior et al.	N/A	N/A
6953461	12/2004	McClurken et al.	N/A	N/A
6958070	12/2004	Witt et al.	N/A	N/A
D511145	12/2004	Donofrio et al.	N/A	N/A
6974450	12/2004	Weber et al.	N/A	N/A
6976844	12/2004	Hickok et al.	N/A	N/A
6976969	12/2004	Messerly	N/A	N/A
6977495	12/2004	Donofrio	N/A	N/A
6979332	12/2004	Adams	N/A	N/A
6981628	12/2005	Wales	N/A	N/A
6984220	12/2005	Wuchinich	N/A	N/A
6984231	12/2005	Goble et al.	N/A	N/A
6988295	12/2005	Tillim	N/A	N/A
6994708	12/2005	Manzo	N/A	N/A
6994709	12/2005	Lida	N/A	N/A
7000818	12/2005	Shelton, IV et al.	N/A	N/A
7001335	12/2005	Adachi et al.	N/A	N/A
7001379	12/2005	Behl et al.	N/A	N/A
7001382	12/2005	Gallo, Sr.	N/A	N/A
7004951	12/2005	Gibbens, III	N/A	N/A
7011657	12/2005	Truckai et al.	N/A	N/A
7014638	12/2005	Michelson	N/A	N/A
7018389	12/2005	Camerlengo	N/A	N/A
7025732	12/2005	Thompson et al.	N/A	N/A
7033356	12/2005	Latterell et al.	N/A	N/A
7033357	12/2005	Baxter et al.	N/A	N/A
7037306	12/2005	Podany et al.	N/A	N/A
7041083	12/2005	Chu et al.	N/A	N/A
7041088	12/2005	Nawrocki et al.	N/A	N/A
7041102	12/2005	Truckai et al.	N/A	N/A
7044949	12/2005	Orszulak et al.	N/A	N/A
7052494	12/2005	Goble et al.	N/A	N/A
7052496	12/2005	Yamauchi	N/A	N/A
7055731	12/2005	Shelton, IV et al.	N/A	N/A
7063699	12/2005	Hess et al.	N/A	N/A
7066893	12/2005	Hibner et al.	N/A	N/A
7066895	12/2005	Podany	N/A	N/A
7066936	12/2005	Ryan	N/A	N/A
7070597	12/2005	Truckai et al.	N/A	N/A
7074218	12/2005	Washington et al.	N/A	N/A
7074219	12/2005	Levine et al.	N/A	N/A
7077039	12/2005	Gass et al.	N/A	N/A
7077845	12/2005	Hacker et al.	N/A	N/A
7077853	12/2005	Kramer et al.	N/A	N/A
7083075	12/2005	Swayze et al.	N/A	N/A

7083613	12/2005	Treat	N/A	N/A
7083618	12/2005	Couture et al.	N/A	N/A
7083619	12/2005	Truckai et al.	N/A	N/A
7087054	12/2005	Truckai et al.	N/A	N/A
7090637	12/2005	Danitz et al.	N/A	N/A
7090672	12/2005	Underwood et al.	N/A	N/A
7094235	12/2005	Francischelli	N/A	N/A
7101371	12/2005	Dycus et al.	N/A	N/A
7101372	12/2005	Dycus et al.	N/A	N/A
7101373	12/2005	Dycus et al.	N/A	N/A
7101378	12/2005	Salameh et al.	N/A	N/A
7104834	12/2005	Robinson et al.	N/A	N/A
7108695	12/2005	Witt et al.	N/A	N/A
7111769	12/2005	Wales et al.	N/A	N/A
7112201	12/2005	Truckai et al.	N/A	N/A
7113831	12/2005	Hooven	N/A	N/A
D531311	12/2005	Guerra et al.	N/A	N/A
7117034	12/2005	Kronberg	N/A	N/A
7118564	12/2005	Ritchie et al.	N/A	N/A
7118570	12/2005	Tetzlaff et al.	N/A	N/A
7118587	12/2005	Dycus et al.	N/A	N/A
7119516	12/2005	Denning	N/A	N/A
7124932	12/2005	Isaacson et al.	N/A	N/A
7125409	12/2005	Truckai et al.	N/A	N/A
7128720	12/2005	Podany	N/A	N/A
7131860	12/2005	Sartor et al.	N/A	N/A
7131970	12/2005	Moses et al.	N/A	N/A
7135018	12/2005	Ryan et al.	N/A	N/A
7135030	12/2005	Schwemberger et al.	N/A	N/A
7137980	12/2005	Buyse et al.	N/A	N/A
7143925	12/2005	Shelton, IV et al.	N/A	N/A
7144403	12/2005	Booth	N/A	N/A
7147138	12/2005	Shelton, IV	N/A	N/A
7153315	12/2005	Miller	N/A	N/A
D536093	12/2006	Nakajima et al.	N/A	N/A
7156189	12/2006	Bar-Cohen et al.	N/A	N/A
7156846	12/2006	Dycus et al.	N/A	N/A
7156853	12/2006	Muratsu	N/A	N/A
7157058	12/2006	Marhasin et al.	N/A	N/A
7159750	12/2006	Racenet et al.	N/A	N/A
7160259	12/2006	Tardy et al.	N/A	N/A
7160296	12/2006	Pearson et al.	N/A	N/A
7160298	12/2006	Lawes et al.	N/A	N/A
7160299	12/2006	Baily	N/A	N/A
7163548	12/2006	Stulen et al.	N/A	N/A
7166103	12/2006	Carmel et al.	N/A	N/A
7169144	12/2006	Hoey et al.	N/A	N/A
7169146	12/2006	Truckai et al.	N/A	N/A
7169156	12/2006	Hart	N/A	N/A

7179254	12/2006	Pendekanti et al.	N/A	N/A
7179271	12/2006	Friedman et al.	N/A	N/A
7186253	12/2006	Truckai et al.	N/A	N/A
7189233	12/2006	Truckai et al.	N/A	N/A
7195631	12/2006	Dumbauld	N/A	N/A
D541418	12/2006	Schechter et al.	N/A	N/A
7198635	12/2006	Danek et al.	N/A	N/A
7204820	12/2006	Akahoshi	N/A	N/A
7207471	12/2006	Heinrich et al.	N/A	N/A
7207997	12/2006	Shipp et al.	N/A	N/A
7208005	12/2006	Frecker et al.	N/A	N/A
7210881	12/2006	Greenberg	N/A	N/A
7211079	12/2006	Treat	N/A	N/A
7217128	12/2006	Atkin et al.	N/A	N/A
7217269	12/2006	El-Galley et al.	N/A	N/A
7220951	12/2006	Truckai et al.	N/A	N/A
7223229	12/2006	Inman et al.	N/A	N/A
7225964	12/2006	Mastri et al.	N/A	N/A
7226447	12/2006	Uchida et al.	N/A	N/A
7226448	12/2006	Bertolero et al.	N/A	N/A
7229455	12/2006	Sakurai et al.	N/A	N/A
7232440	12/2006	Dumbauld et al.	N/A	N/A
7235071	12/2006	Gonnering	N/A	N/A
7235073	12/2006	Levine et al.	N/A	N/A
7241294	12/2006	Reschke	N/A	N/A
7244262	12/2006	Wiener et al.	N/A	N/A
7251531	12/2006	Mosher et al.	N/A	N/A
7252641	12/2006	Thompson et al.	N/A	N/A
7252667	12/2006	Moses et al.	N/A	N/A
7258688	12/2006	Shah et al.	N/A	N/A
7264618	12/2006	Murakami et al.	N/A	N/A
7267677	12/2006	Johnson et al.	N/A	N/A
7267685	12/2006	Butaric et al.	N/A	N/A
7269873	12/2006	Brewer et al.	N/A	N/A
7273483	12/2006	Wiener et al.	N/A	N/A
D552241	12/2006	Bromley et al.	N/A	N/A
7282048	12/2006	Goble et al.	N/A	N/A
7285895	12/2006	Beaupre	N/A	N/A
7287682	12/2006	Ezzat et al.	N/A	N/A
7297149	12/2006	Vitali et al.	N/A	N/A
7300431	12/2006	Dubrovsky	N/A	N/A
7300435	12/2006	Wham et al.	N/A	N/A
7300446	12/2006	Beaupre	N/A	N/A
7300450	12/2006	Vleugels et al.	N/A	N/A
7303531	12/2006	Lee et al.	N/A	N/A
7303557	12/2006	Wham et al.	N/A	N/A
7306597	12/2006	Manzo	N/A	N/A
7307313	12/2006	Ohyanagi et al.	N/A	N/A
7309849	12/2006	Truckai et al.	N/A	N/A
7311706	12/2006	Schoenman et al.	N/A	N/A

7311709	12/2006	Truckai et al.	N/A	N/A
7317955	12/2007	McGreevy	N/A	N/A
7318831	12/2007	Alvarez et al.	N/A	N/A
7318832	12/2007	Young et al.	N/A	N/A
7326236	12/2007	Andreas et al.	N/A	N/A
7329257	12/2007	Kanehira et al.	N/A	N/A
7331410	12/2007	Yong et al.	N/A	N/A
7335165	12/2007	Truwit et al.	N/A	N/A
7335997	12/2007	Wiener	N/A	N/A
7337010	12/2007	Howard et al.	N/A	N/A
7353068	12/2007	Tanaka et al.	N/A	N/A
7354440	12/2007	Truckal et al.	N/A	N/A
7357287	12/2007	Shelton, IV et al.	N/A	N/A
7357802	12/2007	Palanker et al.	N/A	N/A
7361172	12/2007	Cimino	N/A	N/A
7364577	12/2007	Wham et al.	N/A	N/A
7367976	12/2007	Lawes et al.	N/A	N/A
7371227	12/2007	Zeiner	N/A	N/A
RE40388	12/2007	Gines	N/A	N/A
7380695	12/2007	Doll et al.	N/A	N/A
7380696	12/2007	Shelton, IV et al.	N/A	N/A
7381209	12/2007	Truckai et al.	N/A	N/A
7384420	12/2007	Dycus et al.	N/A	N/A
7390317	12/2007	Taylor et al.	N/A	N/A
7396356	12/2007	Mollenauer	N/A	N/A
7403224	12/2007	Fuller et al.	N/A	N/A
7404508	12/2007	Smith et al.	N/A	N/A
7407077	12/2007	Ortiz et al.	N/A	N/A
7408288	12/2007	Hara	N/A	N/A
7412008	12/2007	Lliev	N/A	N/A
7416101	12/2007	Shelton, IV et al.	N/A	N/A
7416437	12/2007	Sartor et al.	N/A	N/A
D576725	12/2007	Shumer et al.	N/A	N/A
7419490	12/2007	Falkenstein et al.	N/A	N/A
7422139	12/2007	Shelton, IV et al.	N/A	N/A
7422463	12/2007	Kuo	N/A	N/A
7422582	12/2007	Malackowski et al.	N/A	N/A
D578643	12/2007	Shumer et al.	N/A	N/A
D578644	12/2007	Shumer et al.	N/A	N/A
D578645	12/2007	Shumer et al.	N/A	N/A
7431694	12/2007	Stefanchik et al.	N/A	N/A
7431704	12/2007	Babaev	N/A	N/A
7431720	12/2007	Pendekanti et al.	N/A	N/A
7435582	12/2007	Zimmermann et al.	N/A	N/A
7441684	12/2007	Shelton, IV et al.	N/A	N/A
7442193	12/2007	Shields et al.	N/A	N/A
7445621	12/2007	Dumbauld et al.	N/A	N/A
7449004	12/2007	Yamada et al.	N/A	N/A
7451904	12/2007	Shelton, IV	N/A	N/A
7455208	12/2007	Wales et al.	N/A	N/A

7455641	12/2007	Yamada et al.	N/A	N/A
7462181	12/2007	Kraft et al.	N/A	N/A
7464846	12/2007	Shelton, IV et al.	N/A	N/A
7464849	12/2007	Shelton, IV et al.	N/A	N/A
7472815	12/2008	Shelton, IV et al.	N/A	N/A
7473145	12/2008	Ehr et al.	N/A	N/A
7473253	12/2008	Dycus et al.	N/A	N/A
7473263	12/2008	Johnston et al.	N/A	N/A
7479148	12/2008	Beaupre	N/A	N/A
7479160	12/2008	Branch et al.	N/A	N/A
7481775	12/2008	Weikel, Jr. et al.	N/A	N/A
7488285	12/2008	Honda et al.	N/A	N/A
7488319	12/2008	Yates	N/A	N/A
7491201	12/2008	Shields et al.	N/A	N/A
7491202	12/2008	Odom et al.	N/A	N/A
7494468	12/2008	Rabiner et al.	N/A	N/A
7494501	12/2008	Ahlberg et al.	N/A	N/A
7498080	12/2008	Tung et al.	N/A	N/A
7502234	12/2008	Goliszek et al.	N/A	N/A
7503893	12/2008	Kucklick	N/A	N/A
7503895	12/2008	Rabiner et al.	N/A	N/A
7506790	12/2008	Shelton, IV	N/A	N/A
7506791	12/2008	Omaits et al.	N/A	N/A
7507239	12/2008	Shadduck	N/A	N/A
7510107	12/2008	Timm et al.	N/A	N/A
7510556	12/2008	Nguyen et al.	N/A	N/A
7513025	12/2008	Fischer	N/A	N/A
7517349	12/2008	Truckai et al.	N/A	N/A
7520865	12/2008	Radley Young et al.	N/A	N/A
7524320	12/2008	Tierney et al.	N/A	N/A
7525309	12/2008	Sherman et al.	N/A	N/A
7530986	12/2008	Beaupre et al.	N/A	N/A
7534243	12/2008	Chin et al.	N/A	N/A
7535233	12/2008	Kojovic et al.	N/A	N/A
D594983	12/2008	Price et al.	N/A	N/A
7540871	12/2008	Gonnering	N/A	N/A
7540872	12/2008	Schechter et al.	N/A	N/A
7543730	12/2008	Marczyk	N/A	N/A
7544200	12/2008	Houser	N/A	N/A
7549564	12/2008	Boudreaux	N/A	N/A
7550216	12/2008	Ofer et al.	N/A	N/A
7553309	12/2008	Buysse et al.	N/A	N/A
7554343	12/2008	Bromfield	N/A	N/A
7559450	12/2008	Wales et al.	N/A	N/A
7559452	12/2008	Wales et al.	N/A	N/A
7563259	12/2008	Takahashi	N/A	N/A
7566318	12/2008	Haefner	N/A	N/A
7567012	12/2008	Namikawa	N/A	N/A
7568603	12/2008	Shelton, IV et al.	N/A	N/A
7569057	12/2008	Liu et al.	N/A	N/A

7572266	12/2008	Young et al.	N/A	N/A
7572268	12/2008	Babaev	N/A	N/A
7578820	12/2008	Moore et al.	N/A	N/A
7582084	12/2008	Swanson et al.	N/A	N/A
7582086	12/2008	Privitera et al.	N/A	N/A
7582087	12/2008	Tetzlaff et al.	N/A	N/A
7582095	12/2008	Shipp et al.	N/A	N/A
7585181	12/2008	Olsen	N/A	N/A
7586289	12/2008	Andruk et al.	N/A	N/A
7587536	12/2008	McLeod	N/A	N/A
7588176	12/2008	Timm et al.	N/A	N/A
7588177	12/2008	Racenet	N/A	N/A
7594925	12/2008	Danek et al.	N/A	N/A
7597693	12/2008	Garrison	N/A	N/A
7601119	12/2008	Shahinian	N/A	N/A
7601136	12/2008	Akahoshi	N/A	N/A
7604150	12/2008	Boudreaux	N/A	N/A
7607557	12/2008	Shelton, IV et al.	N/A	N/A
7617961	12/2008	Viola	N/A	N/A
7621930	12/2008	Houser	N/A	N/A
7625370	12/2008	Hart et al.	N/A	N/A
7628791	12/2008	Garrison et al.	N/A	N/A
7628792	12/2008	Guerra	N/A	N/A
7632267	12/2008	Dahla	N/A	N/A
7632269	12/2008	Truckai et al.	N/A	N/A
7637410	12/2008	Marczyk	N/A	N/A
7641653	12/2009	Dalla Betta et al.	N/A	N/A
7641671	12/2009	Crainich	N/A	N/A
7644848	12/2009	Swayze et al.	N/A	N/A
7645240	12/2009	Thompson et al.	N/A	N/A
7645277	12/2009	McClurken et al.	N/A	N/A
7645278	12/2009	Ichihashi et al.	N/A	N/A
7648499	12/2009	Orszulak et al.	N/A	N/A
7649410	12/2009	Andersen et al.	N/A	N/A
7654431	12/2009	Hueil et al.	N/A	N/A
7655003	12/2009	Lorang et al.	N/A	N/A
7658311	12/2009	Boudreaux	N/A	N/A
7659833	12/2009	Warner et al.	N/A	N/A
7662151	12/2009	Crompton, Jr. et al.	N/A	N/A
7665647	12/2009	Shelton, IV et al.	N/A	N/A
7666206	12/2009	Taniguchi et al.	N/A	N/A
7667592	12/2009	Ohyama et al.	N/A	N/A
7670334	12/2009	Hueil et al.	N/A	N/A
7670338	12/2009	Albrecht et al.	N/A	N/A
7674263	12/2009	Ryan	N/A	N/A
7678069	12/2009	Baker et al.	N/A	N/A
7678105	12/2009	McGreevy et al.	N/A	N/A
7678125	12/2009	Shipp	N/A	N/A
7682366	12/2009	Sakurai et al.	N/A	N/A
7686770	12/2009	Cohen	N/A	N/A

7686826	12/2009	Lee et al.	N/A	N/A
7688028	12/2009	Phillips et al.	N/A	N/A
7691095	12/2009	Bednarek et al.	N/A	N/A
7691098	12/2009	Wallace et al.	N/A	N/A
7696441	12/2009	Kataoka	N/A	N/A
7699846	12/2009	Ryan	N/A	N/A
7703459	12/2009	Saadat et al.	N/A	N/A
7703653	12/2009	Shah et al.	N/A	N/A
7708735	12/2009	Chapman et al.	N/A	N/A
7708751	12/2009	Hughes et al.	N/A	N/A
7708758	12/2009	Lee et al.	N/A	N/A
7708768	12/2009	Danek et al.	N/A	N/A
7713202	12/2009	Boukhny et al.	N/A	N/A
7713267	12/2009	Pozzato	N/A	N/A
7714481	12/2009	Sakai	N/A	N/A
7717312	12/2009	Beetel	N/A	N/A
7717914	12/2009	Kimura	N/A	N/A
7717915	12/2009	Miyazawa	N/A	N/A
7721935	12/2009	Racenet et al.	N/A	N/A
7722527	12/2009	Bouchier et al.	N/A	N/A
7722607	12/2009	Dumbauld et al.	N/A	N/A
D618797	12/2009	Price et al.	N/A	N/A
7726537	12/2009	Olson et al.	N/A	N/A
7727177	12/2009	Bayat	N/A	N/A
7731717	12/2009	Odom et al.	N/A	N/A
7738969	12/2009	Bleich	N/A	N/A
7740594	12/2009	Hibner	N/A	N/A
7744615	12/2009	Couture	N/A	N/A
7749240	12/2009	Takahashi et al.	N/A	N/A
7751115	12/2009	Song	N/A	N/A
7753245	12/2009	Boudreaux et al.	N/A	N/A
7753904	12/2009	Shelton, IV et al.	N/A	N/A
7753908	12/2009	Swanson	N/A	N/A
7762445	12/2009	Heinrich et al.	N/A	N/A
D621503	12/2009	Otten et al.	N/A	N/A
7766210	12/2009	Shelton, IV et al.	N/A	N/A
7766693	12/2009	Sartor et al.	N/A	N/A
7766910	12/2009	Hixson et al.	N/A	N/A
7768510	12/2009	Tsai et al.	N/A	N/A
7770774	12/2009	Mastri et al.	N/A	N/A
7770775	12/2009	Shelton, IV et al.	N/A	N/A
7771425	12/2009	Dycus et al.	N/A	N/A
7771444	12/2009	Patel et al.	N/A	N/A
7775972	12/2009	Brock et al.	N/A	N/A
7776036	12/2009	Schechter et al.	N/A	N/A
7776037	12/2009	Odom	N/A	N/A
7778733	12/2009	Nowlin et al.	N/A	N/A
7780054	12/2009	Wales	N/A	N/A
7780593	12/2009	Ueno et al.	N/A	N/A
7780651	12/2009	Madhani et al.	N/A	N/A

7780659	12/2009	Okada et al.	N/A	N/A
7780663	12/2009	Yates et al.	N/A	N/A
7784662	12/2009	Wales et al.	N/A	N/A
7784663	12/2009	Shelton, IV	N/A	N/A
7789883	12/2009	Takashino et al.	N/A	N/A
7793814	12/2009	Racenet et al.	N/A	N/A
7794475	12/2009	Hess et al.	N/A	N/A
7796969	12/2009	Kelly et al.	N/A	N/A
7798386	12/2009	Schall et al.	N/A	N/A
7799020	12/2009	Shores et al.	N/A	N/A
7799027	12/2009	Hafner	N/A	N/A
7799045	12/2009	Masuda	N/A	N/A
7803151	12/2009	Whitman	N/A	N/A
7803152	12/2009	Honda et al.	N/A	N/A
7803156	12/2009	Eder et al.	N/A	N/A
7803168	12/2009	Gifford et al.	N/A	N/A
7806891	12/2009	Nowlin et al.	N/A	N/A
7810693	12/2009	Broehl et al.	N/A	N/A
7811283	12/2009	Moses et al.	N/A	N/A
7815238	12/2009	Cao	N/A	N/A
7815641	12/2009	Dodde et al.	N/A	N/A
7819298	12/2009	Hall et al.	N/A	N/A
7819299	12/2009	Shelton, IV et al.	N/A	N/A
7819819	12/2009	Quick et al.	N/A	N/A
7819872	12/2009	Johnson et al.	N/A	N/A
7821143	12/2009	Wiener	N/A	N/A
D627066	12/2009	Romero	N/A	N/A
7824401	12/2009	Manzo et al.	N/A	N/A
7832408	12/2009	Shelton, IV et al.	N/A	N/A
7832611	12/2009	Boyden et al.	N/A	N/A
7832612	12/2009	Baxter, III et al.	N/A	N/A
7834484	12/2009	Sartor	N/A	N/A
7837699	12/2009	Yamada et al.	N/A	N/A
7845537	12/2009	Shelton, IV et al.	N/A	N/A
7846155	12/2009	Houser et al.	N/A	N/A
7846159	12/2009	Morrison et al.	N/A	N/A
7846160	12/2009	Payne et al.	N/A	N/A
7846161	12/2009	Dumbauld et al.	N/A	N/A
7854735	12/2009	Houser et al.	N/A	N/A
D631155	12/2010	Peine et al.	N/A	N/A
7861906	12/2010	Doll et al.	N/A	N/A
7862560	12/2010	Marion	N/A	N/A
7862561	12/2010	Swanson et al.	N/A	N/A
7867228	12/2010	Nobis et al.	N/A	N/A
7871392	12/2010	Sartor	N/A	N/A
7871423	12/2010	Livneh	N/A	N/A
7876030	12/2010	Taki et al.	N/A	N/A
D631965	12/2010	Price et al.	N/A	N/A
7877852	12/2010	Unger et al.	N/A	N/A
7878991	12/2010	Babaev	N/A	N/A

7879029	12/2010	Jimenez	N/A	N/A
7879033	12/2010	Sartor et al.	N/A	N/A
7879035	12/2010	Garrison et al.	N/A	N/A
7879070	12/2010	Ortiz et al.	N/A	N/A
7883475	12/2010	Dupont et al.	N/A	N/A
7892606	12/2010	Thies et al.	N/A	N/A
7896875	12/2010	Heim et al.	N/A	N/A
7897792	12/2010	Iikura et al.	N/A	N/A
7901400	12/2010	Wham et al.	N/A	N/A
7901423	12/2010	Stulen et al.	N/A	N/A
7905881	12/2010	Masuda et al.	N/A	N/A
7909220	12/2010	Viola	N/A	N/A
7909820	12/2010	Lipson et al.	N/A	N/A
7909824	12/2010	Masuda et al.	N/A	N/A
7918848	12/2010	Lau et al.	N/A	N/A
7919184	12/2010	Mohapatra et al.	N/A	N/A
7922061	12/2010	Shelton, IV et al.	N/A	N/A
7922651	12/2010	Yamada et al.	N/A	N/A
7931611	12/2010	Novak et al.	N/A	N/A
7931649	12/2010	Couture et al.	N/A	N/A
D637288	12/2010	Houghton	N/A	N/A
D638540	12/2010	Ijiri et al.	N/A	N/A
7935114	12/2010	Takashino et al.	N/A	N/A
7936203	12/2010	Zimlich	N/A	N/A
7951095	12/2010	Makin et al.	N/A	N/A
7951165	12/2010	Golden et al.	N/A	N/A
7954682	12/2010	Giordano et al.	N/A	N/A
7955331	12/2010	Truckai et al.	N/A	N/A
7956620	12/2010	Gilbert	N/A	N/A
7959050	12/2010	Smith et al.	N/A	N/A
7959626	12/2010	Hong et al.	N/A	N/A
7963963	12/2010	Francischelli et al.	N/A	N/A
7967602	12/2010	Lindquist	N/A	N/A
7972328	12/2010	Wham et al.	N/A	N/A
7972329	12/2010	Refior et al.	N/A	N/A
7975895	12/2010	Milliman	N/A	N/A
7976544	12/2010	McClurken et al.	N/A	N/A
7980443	12/2010	Scheib et al.	N/A	N/A
7981050	12/2010	Ritchart et al.	N/A	N/A
7981113	12/2010	Truckai et al.	N/A	N/A
7997278	12/2010	Utlely et al.	N/A	N/A
7998157	12/2010	Culp et al.	N/A	N/A
8002732	12/2010	Visconti	N/A	N/A
8002770	12/2010	Swanson et al.	N/A	N/A
8020743	12/2010	Shelton, IV	N/A	N/A
8025672	12/2010	Novak et al.	N/A	N/A
8028885	12/2010	Smith et al.	N/A	N/A
8033173	12/2010	Ehlert et al.	N/A	N/A
8034049	12/2010	Odom et al.	N/A	N/A
8038693	12/2010	Allen	N/A	N/A

8048070	12/2010	O'Brien et al.	N/A	N/A
8048074	12/2010	Masuda	N/A	N/A
8052672	12/2010	Laufer et al.	N/A	N/A
8055208	12/2010	Lilla et al.	N/A	N/A
8056720	12/2010	Hawkes	N/A	N/A
8056787	12/2010	Boudreaux et al.	N/A	N/A
8057468	12/2010	Konesky	N/A	N/A
8057498	12/2010	Robertson	N/A	N/A
8058771	12/2010	Giordano et al.	N/A	N/A
8061014	12/2010	Smith et al.	N/A	N/A
8066167	12/2010	Measamer et al.	N/A	N/A
8070036	12/2010	Knodel	N/A	N/A
8070711	12/2010	Bassinger et al.	N/A	N/A
8070762	12/2010	Escudero et al.	N/A	N/A
8075555	12/2010	Truckai et al.	N/A	N/A
8075558	12/2010	Truckai et al.	N/A	N/A
8089197	12/2011	Rinner et al.	N/A	N/A
8092475	12/2011	Cotter et al.	N/A	N/A
8096459	12/2011	Ortiz et al.	N/A	N/A
8097012	12/2011	Kagarise	N/A	N/A
8100894	12/2011	Mucko et al.	N/A	N/A
8105230	12/2011	Honda et al.	N/A	N/A
8105323	12/2011	Buysse et al.	N/A	N/A
8105324	12/2011	Palanker et al.	N/A	N/A
8114104	12/2011	Young et al.	N/A	N/A
8118276	12/2011	Sanders et al.	N/A	N/A
8128624	12/2011	Couture et al.	N/A	N/A
8133218	12/2011	Daw et al.	N/A	N/A
8136712	12/2011	Zingman	N/A	N/A
8141762	12/2011	Bedi et al.	N/A	N/A
8142421	12/2011	Cooper et al.	N/A	N/A
8142461	12/2011	Houser et al.	N/A	N/A
8147485	12/2011	Wham et al.	N/A	N/A
8147488	12/2011	Masuda	N/A	N/A
8147508	12/2011	Madan et al.	N/A	N/A
8152801	12/2011	Goldberg et al.	N/A	N/A
8152825	12/2011	Madan et al.	N/A	N/A
8157145	12/2011	Shelton, IV et al.	N/A	N/A
8161977	12/2011	Shelton, IV et al.	N/A	N/A
8162966	12/2011	Connor et al.	N/A	N/A
8170717	12/2011	Sutherland et al.	N/A	N/A
8172846	12/2011	Brunnett et al.	N/A	N/A
8172870	12/2011	Shipp	N/A	N/A
8177800	12/2011	Spitz et al.	N/A	N/A
8182502	12/2011	Stulen et al.	N/A	N/A
8186560	12/2011	Hess et al.	N/A	N/A
8186877	12/2011	Klimovitch et al.	N/A	N/A
8187267	12/2011	Pappone et al.	N/A	N/A
D661801	12/2011	Price et al.	N/A	N/A
D661802	12/2011	Price et al.	N/A	N/A

D661803	12/2011	Price et al.	N/A	N/A
D661804	12/2011	Price et al.	N/A	N/A
8197472	12/2011	Lau et al.	N/A	N/A
8197479	12/2011	Olson et al.	N/A	N/A
8197502	12/2011	Smith et al.	N/A	N/A
8207651	12/2011	Gilbert	N/A	N/A
8210411	12/2011	Yates et al.	N/A	N/A
8211100	12/2011	Podhajsky et al.	N/A	N/A
8216223	12/2011	Wham et al.	N/A	N/A
8220688	12/2011	Laurent et al.	N/A	N/A
8221306	12/2011	Okada et al.	N/A	N/A
8221415	12/2011	Francischelli	N/A	N/A
8221418	12/2011	Prakash et al.	N/A	N/A
8226580	12/2011	Govari et al.	N/A	N/A
8226665	12/2011	Cohen	N/A	N/A
8226675	12/2011	Houser et al.	N/A	N/A
8231607	12/2011	Takuma	N/A	N/A
8235917	12/2011	Joseph et al.	N/A	N/A
8236018	12/2011	Yoshimine et al.	N/A	N/A
8236019	12/2011	Houser	N/A	N/A
8236020	12/2011	Smith et al.	N/A	N/A
8241235	12/2011	Kahler et al.	N/A	N/A
8241271	12/2011	Millman et al.	N/A	N/A
8241282	12/2011	Unger et al.	N/A	N/A
8241283	12/2011	Guerra et al.	N/A	N/A
8241284	12/2011	Dycus et al.	N/A	N/A
8241312	12/2011	Messerly	N/A	N/A
8246575	12/2011	Viola	N/A	N/A
8246615	12/2011	Behnke	N/A	N/A
8246616	12/2011	Amoah et al.	N/A	N/A
8246618	12/2011	Bucciaglia et al.	N/A	N/A
8246642	12/2011	Houser et al.	N/A	N/A
8251994	12/2011	McKenna et al.	N/A	N/A
8252012	12/2011	Stulen	N/A	N/A
8253303	12/2011	Giordano et al.	N/A	N/A
8257377	12/2011	Wiener et al.	N/A	N/A
8257387	12/2011	Cunningham	N/A	N/A
8262563	12/2011	Bakos et al.	N/A	N/A
8267300	12/2011	Boudreaux	N/A	N/A
8267935	12/2011	Couture et al.	N/A	N/A
8273087	12/2011	Kimura et al.	N/A	N/A
D669992	12/2011	Schafer et al.	N/A	N/A
D669993	12/2011	Merchant et al.	N/A	N/A
8277446	12/2011	Heard	N/A	N/A
8277447	12/2011	Garrison et al.	N/A	N/A
8277471	12/2011	Wiener et al.	N/A	N/A
8282581	12/2011	Zhao et al.	N/A	N/A
8282669	12/2011	Gerber et al.	N/A	N/A
8286846	12/2011	Smith et al.	N/A	N/A
8287485	12/2011	Kimura et al.	N/A	N/A

8287528	12/2011	Wham et al.	N/A	N/A
8287532	12/2011	Carroll et al.	N/A	N/A
8292886	12/2011	Kerr et al.	N/A	N/A
8292888	12/2011	Whitman	N/A	N/A
8292905	12/2011	Taylor et al.	N/A	N/A
8295902	12/2011	Salahieh et al.	N/A	N/A
8298223	12/2011	Wham et al.	N/A	N/A
8298225	12/2011	Gilbert	N/A	N/A
8298232	12/2011	Unger	N/A	N/A
8298233	12/2011	Mueller	N/A	N/A
8303576	12/2011	Brock	N/A	N/A
8303579	12/2011	Shibata	N/A	N/A
8303580	12/2011	Wham et al.	N/A	N/A
8303583	12/2011	Hosier et al.	N/A	N/A
8303613	12/2011	Crandall et al.	N/A	N/A
8306629	12/2011	Mioduski et al.	N/A	N/A
8308040	12/2011	Huang et al.	N/A	N/A
8308721	12/2011	Shibata et al.	N/A	N/A
8319400	12/2011	Houser et al.	N/A	N/A
8323302	12/2011	Robertson et al.	N/A	N/A
8323310	12/2011	Kingsley	N/A	N/A
8328061	12/2011	Kasvikis	N/A	N/A
8328761	12/2011	Widenhouse et al.	N/A	N/A
8328802	12/2011	Deville et al.	N/A	N/A
8328833	12/2011	Cuny	N/A	N/A
8328834	12/2011	Isaacs et al.	N/A	N/A
8333764	12/2011	Francischelli et al.	N/A	N/A
8333778	12/2011	Smith et al.	N/A	N/A
8333779	12/2011	Smith et al.	N/A	N/A
8334468	12/2011	Palmer et al.	N/A	N/A
8334635	12/2011	Voegele et al.	N/A	N/A
8337407	12/2011	Quistgaard et al.	N/A	N/A
8338726	12/2011	Palmer et al.	N/A	N/A
8343146	12/2012	Godara et al.	N/A	N/A
8344596	12/2012	Nield et al.	N/A	N/A
8348880	12/2012	Messerly et al.	N/A	N/A
8348947	12/2012	Takashino et al.	N/A	N/A
8348967	12/2012	Stulen	N/A	N/A
8353297	12/2012	Dacquay et al.	N/A	N/A
8357103	12/2012	Mark et al.	N/A	N/A
8357144	12/2012	Whitman et al.	N/A	N/A
8357149	12/2012	Govari et al.	N/A	N/A
8357158	12/2012	McKenna et al.	N/A	N/A
8360299	12/2012	Zemlok et al.	N/A	N/A
8361066	12/2012	Long et al.	N/A	N/A
8361072	12/2012	Dumbauld et al.	N/A	N/A
8361569	12/2012	Saito et al.	N/A	N/A
8366727	12/2012	Witt et al.	N/A	N/A
8372064	12/2012	Douglass et al.	N/A	N/A
8372099	12/2012	Deville et al.	N/A	N/A

8372101	12/2012	Smith et al.	N/A	N/A
8372102	12/2012	Stulen et al.	N/A	N/A
8374670	12/2012	Selkee	N/A	N/A
8377044	12/2012	Coe et al.	N/A	N/A
8377059	12/2012	Deville et al.	N/A	N/A
8377085	12/2012	Smith et al.	N/A	N/A
8382748	12/2012	Geisel	N/A	N/A
8382775	12/2012	Bender et al.	N/A	N/A
8382782	12/2012	Robertson et al.	N/A	N/A
8382792	12/2012	Chojin	N/A	N/A
8388646	12/2012	Chojin	N/A	N/A
8388647	12/2012	Nau, Jr. et al.	N/A	N/A
8393514	12/2012	Shelton, IV et al.	N/A	N/A
8394115	12/2012	Houser et al.	N/A	N/A
8397971	12/2012	Yates et al.	N/A	N/A
8398394	12/2012	Sauter et al.	N/A	N/A
8398674	12/2012	Prestel	N/A	N/A
8403926	12/2012	Nobis et al.	N/A	N/A
8403945	12/2012	Whitfield et al.	N/A	N/A
8403948	12/2012	Deville et al.	N/A	N/A
8403949	12/2012	Palmer et al.	N/A	N/A
8403950	12/2012	Palmer et al.	N/A	N/A
8409234	12/2012	Stahler et al.	N/A	N/A
8414577	12/2012	Boudreaux et al.	N/A	N/A
8418073	12/2012	Mohr et al.	N/A	N/A
8418349	12/2012	Smith et al.	N/A	N/A
8419757	12/2012	Smith et al.	N/A	N/A
8419758	12/2012	Smith et al.	N/A	N/A
8419759	12/2012	Dietz	N/A	N/A
8423182	12/2012	Robinson et al.	N/A	N/A
8425410	12/2012	Murray et al.	N/A	N/A
8425545	12/2012	Smith et al.	N/A	N/A
8430811	12/2012	Hess et al.	N/A	N/A
8430874	12/2012	Newton et al.	N/A	N/A
8430876	12/2012	Kappus et al.	N/A	N/A
8430897	12/2012	Novak et al.	N/A	N/A
8430898	12/2012	Wiener et al.	N/A	N/A
8435257	12/2012	Smith et al.	N/A	N/A
8437832	12/2012	Govari et al.	N/A	N/A
8439912	12/2012	Cunningham et al.	N/A	N/A
8439939	12/2012	Deville et al.	N/A	N/A
8444036	12/2012	Shelton, IV	N/A	N/A
8444637	12/2012	Podmore et al.	N/A	N/A
8444662	12/2012	Palmer et al.	N/A	N/A
8444663	12/2012	Houser et al.	N/A	N/A
8444664	12/2012	Balanev et al.	N/A	N/A
8453906	12/2012	Huang et al.	N/A	N/A
8454599	12/2012	Inagaki et al.	N/A	N/A
8454639	12/2012	Du et al.	N/A	N/A
8459525	12/2012	Yates et al.	N/A	N/A

8460284	12/2012	Aronow et al.	N/A	N/A
8460288	12/2012	Tamai et al.	N/A	N/A
8460292	12/2012	Truckai et al.	N/A	N/A
8461744	12/2012	Wiener et al.	N/A	N/A
8469981	12/2012	Robertson et al.	N/A	N/A
8471685	12/2012	Shingai	N/A	N/A
8479969	12/2012	Shelton, IV	N/A	N/A
8480703	12/2012	Nicholas et al.	N/A	N/A
8484833	12/2012	Cunningham et al.	N/A	N/A
8485413	12/2012	Scheib et al.	N/A	N/A
8485970	12/2012	Widenhouse et al.	N/A	N/A
8486057	12/2012	Behnke, II	N/A	N/A
8486096	12/2012	Robertson et al.	N/A	N/A
8491578	12/2012	Manwaring et al.	N/A	N/A
8491625	12/2012	Horner	N/A	N/A
8496682	12/2012	Guerra et al.	N/A	N/A
D687549	12/2012	Johnson et al.	N/A	N/A
8506555	12/2012	Ruiz Morales	N/A	N/A
8509318	12/2012	Tailliet	N/A	N/A
8512336	12/2012	Couture	N/A	N/A
8512337	12/2012	Francischelli et al.	N/A	N/A
8512359	12/2012	Whitman et al.	N/A	N/A
8512364	12/2012	Kowalski et al.	N/A	N/A
8512365	12/2012	Wiener et al.	N/A	N/A
8517239	12/2012	Scheib et al.	N/A	N/A
8518067	12/2012	Masuda et al.	N/A	N/A
8521331	12/2012	Itkowitz	N/A	N/A
8523043	12/2012	Ullrich et al.	N/A	N/A
8523882	12/2012	Huitema et al.	N/A	N/A
8523889	12/2012	Stulen et al.	N/A	N/A
8528563	12/2012	Gruber	N/A	N/A
8529437	12/2012	Taylor et al.	N/A	N/A
8529565	12/2012	Masuda et al.	N/A	N/A
8531064	12/2012	Robertson et al.	N/A	N/A
8535308	12/2012	Govari et al.	N/A	N/A
8535311	12/2012	Schall	N/A	N/A
8535340	12/2012	Allen	N/A	N/A
8535341	12/2012	Allen	N/A	N/A
8540128	12/2012	Shelton, IV et al.	N/A	N/A
8546996	12/2012	Messerly et al.	N/A	N/A
8546999	12/2012	Houser et al.	N/A	N/A
8551077	12/2012	Main et al.	N/A	N/A
8551086	12/2012	Kimura et al.	N/A	N/A
8556929	12/2012	Harper et al.	N/A	N/A
8561870	12/2012	Baxter, III et al.	N/A	N/A
8562592	12/2012	Conlon et al.	N/A	N/A
8562598	12/2012	Falkenstein et al.	N/A	N/A
8562600	12/2012	Kirkpatrick et al.	N/A	N/A
8562604	12/2012	Nishimura	N/A	N/A
8568390	12/2012	Mueller	N/A	N/A

8568397	12/2012	Horner et al.	N/A	N/A
8568400	12/2012	Gilbert	N/A	N/A
8568412	12/2012	Brandt et al.	N/A	N/A
8569997	12/2012	Lee	N/A	N/A
8573461	12/2012	Shelton, IV et al.	N/A	N/A
8573465	12/2012	Shelton, IV	N/A	N/A
8574231	12/2012	Boudreaux et al.	N/A	N/A
8574253	12/2012	Gruber et al.	N/A	N/A
8579176	12/2012	Smith et al.	N/A	N/A
8579897	12/2012	Vakharia et al.	N/A	N/A
8579928	12/2012	Robertson et al.	N/A	N/A
8579937	12/2012	Gresham	N/A	N/A
8585727	12/2012	Polo	N/A	N/A
8588371	12/2012	Ogawa et al.	N/A	N/A
8591459	12/2012	Clymer et al.	N/A	N/A
8591506	12/2012	Wham et al.	N/A	N/A
8591536	12/2012	Robertson	N/A	N/A
D695407	12/2012	Price et al.	N/A	N/A
D696631	12/2012	Price et al.	N/A	N/A
8596513	12/2012	Olson et al.	N/A	N/A
8597193	12/2012	Grunwald et al.	N/A	N/A
8597287	12/2012	Benamou et al.	N/A	N/A
8602031	12/2012	Reis et al.	N/A	N/A
8602288	12/2012	Shelton, IV et al.	N/A	N/A
8603085	12/2012	Jimenez	N/A	N/A
8603089	12/2012	Viola	N/A	N/A
8608044	12/2012	Hueil et al.	N/A	N/A
8608045	12/2012	Smith et al.	N/A	N/A
8608745	12/2012	Guzman et al.	N/A	N/A
8613383	12/2012	Beckman et al.	N/A	N/A
8616431	12/2012	Timm et al.	N/A	N/A
8617152	12/2012	Werneth et al.	N/A	N/A
8617194	12/2012	Beaupre	N/A	N/A
8622274	12/2013	Yates et al.	N/A	N/A
8623011	12/2013	Spivey	N/A	N/A
8623016	12/2013	Fischer	N/A	N/A
8623027	12/2013	Price et al.	N/A	N/A
8623040	12/2013	Artsyukhovich et al.	N/A	N/A
8623044	12/2013	Timm et al.	N/A	N/A
8628529	12/2013	Aldridge et al.	N/A	N/A
8628534	12/2013	Jones et al.	N/A	N/A
8632461	12/2013	Glossop	N/A	N/A
8636736	12/2013	Yates et al.	N/A	N/A
8638428	12/2013	Brown	N/A	N/A
8640788	12/2013	Dachs, II et al.	N/A	N/A
8641663	12/2013	Kirschenman et al.	N/A	N/A
8647350	12/2013	Mohan et al.	N/A	N/A
8650728	12/2013	Wan et al.	N/A	N/A
8652120	12/2013	Giordano et al.	N/A	N/A

8652132	12/2013	Tsuchiya et al.	N/A	N/A
8652155	12/2013	Houser et al.	N/A	N/A
8657489	12/2013	Ladurner et al.	N/A	N/A
8659208	12/2013	Rose et al.	N/A	N/A
8663214	12/2013	Weinberg et al.	N/A	N/A
8663220	12/2013	Wiener et al.	N/A	N/A
8663222	12/2013	Anderson et al.	N/A	N/A
8663223	12/2013	Masuda et al.	N/A	N/A
8663262	12/2013	Smith et al.	N/A	N/A
8668691	12/2013	Heard	N/A	N/A
8668710	12/2013	Slipszenko et al.	N/A	N/A
8684253	12/2013	Giordano et al.	N/A	N/A
8685016	12/2013	Wham et al.	N/A	N/A
8685020	12/2013	Weizman et al.	N/A	N/A
8690582	12/2013	Rohrbach et al.	N/A	N/A
8695866	12/2013	Leimbach et al.	N/A	N/A
8696366	12/2013	Chen et al.	N/A	N/A
8696665	12/2013	Hunt et al.	N/A	N/A
8696666	12/2013	Sanai et al.	N/A	N/A
8696917	12/2013	Petisce et al.	N/A	N/A
8702609	12/2013	Hadjicostis	N/A	N/A
8702702	12/2013	Edwards et al.	N/A	N/A
8702704	12/2013	Shelton, IV et al.	N/A	N/A
8704425	12/2013	Giordano et al.	N/A	N/A
8708213	12/2013	Shelton, IV et al.	N/A	N/A
8709008	12/2013	Willis et al.	N/A	N/A
8709031	12/2013	Stulen	N/A	N/A
8709035	12/2013	Johnson et al.	N/A	N/A
8715270	12/2013	Weitzner et al.	N/A	N/A
8715277	12/2013	Weizman	N/A	N/A
8721640	12/2013	Taylor et al.	N/A	N/A
8721657	12/2013	Kondoh et al.	N/A	N/A
8733613	12/2013	Huitema et al.	N/A	N/A
8733614	12/2013	Ross et al.	N/A	N/A
8734443	12/2013	Hixson et al.	N/A	N/A
8738110	12/2013	Tabada et al.	N/A	N/A
8747238	12/2013	Shelton, IV et al.	N/A	N/A
8747351	12/2013	Schultz	N/A	N/A
8747404	12/2013	Boudreaux et al.	N/A	N/A
8749116	12/2013	Messerly et al.	N/A	N/A
8752264	12/2013	Ackley et al.	N/A	N/A
8752749	12/2013	Moore et al.	N/A	N/A
8753338	12/2013	Widenhouse et al.	N/A	N/A
8754570	12/2013	Voegele et al.	N/A	N/A
8758342	12/2013	Bales et al.	N/A	N/A
8758352	12/2013	Cooper et al.	N/A	N/A
8758391	12/2013	Swayze et al.	N/A	N/A
8764735	12/2013	Coe et al.	N/A	N/A
8764747	12/2013	Cummings et al.	N/A	N/A
8767970	12/2013	Eppolito	N/A	N/A

8770459	12/2013	Racenet et al.	N/A	N/A
8771269	12/2013	Sherman et al.	N/A	N/A
8771270	12/2013	Burbank	N/A	N/A
8771293	12/2013	Surti et al.	N/A	N/A
8773001	12/2013	Wiener et al.	N/A	N/A
8777944	12/2013	Frankhouser et al.	N/A	N/A
8777945	12/2013	Floume et al.	N/A	N/A
8779648	12/2013	Giordano et al.	N/A	N/A
8783541	12/2013	Shelton, IV et al.	N/A	N/A
8784415	12/2013	Malackowski et al.	N/A	N/A
8784418	12/2013	Romero	N/A	N/A
8790342	12/2013	Stulen et al.	N/A	N/A
8795274	12/2013	Hanna	N/A	N/A
8795275	12/2013	Hafner	N/A	N/A
8795276	12/2013	Dietz et al.	N/A	N/A
8795327	12/2013	Dietz et al.	N/A	N/A
8800838	12/2013	Shelton, IV	N/A	N/A
8801710	12/2013	Ullrich et al.	N/A	N/A
8801752	12/2013	Fortier et al.	N/A	N/A
8807414	12/2013	Ross et al.	N/A	N/A
8808204	12/2013	Irisawa et al.	N/A	N/A
8808319	12/2013	Houser et al.	N/A	N/A
8814856	12/2013	Elmouelhi et al.	N/A	N/A
8814870	12/2013	Paraschiv et al.	N/A	N/A
8820605	12/2013	Shelton, IV	N/A	N/A
8821388	12/2013	Naito et al.	N/A	N/A
8827992	12/2013	Koss et al.	N/A	N/A
8827995	12/2013	Schaller et al.	N/A	N/A
8831779	12/2013	Ortmaier et al.	N/A	N/A
8834466	12/2013	Cummings et al.	N/A	N/A
8834518	12/2013	Faller et al.	N/A	N/A
8844789	12/2013	Shelton, IV et al.	N/A	N/A
8845537	12/2013	Tanaka et al.	N/A	N/A
8845630	12/2013	Mehta et al.	N/A	N/A
8848808	12/2013	Dress	N/A	N/A
8851354	12/2013	Swensgard et al.	N/A	N/A
8852184	12/2013	Kucklick	N/A	N/A
8858547	12/2013	Brogna	N/A	N/A
8862955	12/2013	Cesari	N/A	N/A
8864749	12/2013	Okada	N/A	N/A
8864757	12/2013	Klimovitch et al.	N/A	N/A
8864761	12/2013	Johnson et al.	N/A	N/A
8870865	12/2013	Frankhouser et al.	N/A	N/A
8874220	12/2013	Draghici et al.	N/A	N/A
8876726	12/2013	Amit et al.	N/A	N/A
8876858	12/2013	Braun	N/A	N/A
8882766	12/2013	Couture et al.	N/A	N/A
8882791	12/2013	Stulen	N/A	N/A
8888776	12/2013	Dietz et al.	N/A	N/A
8888783	12/2013	Young	N/A	N/A

8888809	12/2013	Davison et al.	N/A	N/A
8899462	12/2013	Kostrzewski et al.	N/A	N/A
8900259	12/2013	Houser et al.	N/A	N/A
8906016	12/2013	Boudreaux et al.	N/A	N/A
8906017	12/2013	Rioux et al.	N/A	N/A
8911438	12/2013	Swoyer et al.	N/A	N/A
8911460	12/2013	Neurohr et al.	N/A	N/A
8920412	12/2013	Fritz et al.	N/A	N/A
8920414	12/2013	Stone et al.	N/A	N/A
8920421	12/2013	Rupp	N/A	N/A
8926607	12/2014	Norvell et al.	N/A	N/A
8926608	12/2014	Bacher et al.	N/A	N/A
8926620	12/2014	Chasmawala et al.	N/A	N/A
8931682	12/2014	Timm et al.	N/A	N/A
8932282	12/2014	Gilbert	N/A	N/A
8932299	12/2014	Bono et al.	N/A	N/A
8936614	12/2014	Allen, IV	N/A	N/A
8939974	12/2014	Boudreaux et al.	N/A	N/A
8945126	12/2014	Garrison et al.	N/A	N/A
8951248	12/2014	Messerly et al.	N/A	N/A
8951272	12/2014	Robertson et al.	N/A	N/A
8956349	12/2014	Aldridge et al.	N/A	N/A
8960520	12/2014	McCuen	N/A	N/A
8961515	12/2014	Twomey et al.	N/A	N/A
8961547	12/2014	Dietz et al.	N/A	N/A
8967443	12/2014	McCuen	N/A	N/A
8968283	12/2014	Kharin	N/A	N/A
8968294	12/2014	Maass et al.	N/A	N/A
8968296	12/2014	McPherson	N/A	N/A
8968355	12/2014	Malkowski et al.	N/A	N/A
8974447	12/2014	Kimball et al.	N/A	N/A
8974477	12/2014	Yamada	N/A	N/A
8974479	12/2014	Ross et al.	N/A	N/A
8974932	12/2014	McGahan et al.	N/A	N/A
8979843	12/2014	Timm et al.	N/A	N/A
8979844	12/2014	White et al.	N/A	N/A
8979890	12/2014	Boudreaux	N/A	N/A
8986287	12/2014	Park et al.	N/A	N/A
8986297	12/2014	Daniel et al.	N/A	N/A
8986302	12/2014	Aldridge et al.	N/A	N/A
8989855	12/2014	Murphy et al.	N/A	N/A
8989903	12/2014	Weir et al.	N/A	N/A
8991678	12/2014	Wellman et al.	N/A	N/A
8992422	12/2014	Spivey et al.	N/A	N/A
8992526	12/2014	Brodbeck et al.	N/A	N/A
8998891	12/2014	Garito et al.	N/A	N/A
9005199	12/2014	Beckman et al.	N/A	N/A
9011437	12/2014	Woodruff et al.	N/A	N/A
9011471	12/2014	Timm et al.	N/A	N/A
9017326	12/2014	DiNardo et al.	N/A	N/A

9017355	12/2014	Smith et al.	N/A	N/A
9017370	12/2014	Reschke et al.	N/A	N/A
9017372	12/2014	Artale et al.	N/A	N/A
9023035	12/2014	Allen, IV et al.	N/A	N/A
9023070	12/2014	Levine et al.	N/A	N/A
9023071	12/2014	Miller et al.	N/A	N/A
9028397	12/2014	Naito	N/A	N/A
9028476	12/2014	Bonn	N/A	N/A
9028478	12/2014	Mueller	N/A	N/A
9028481	12/2014	Behnke, II	N/A	N/A
9028494	12/2014	Shelton, IV et al.	N/A	N/A
9028519	12/2014	Yates et al.	N/A	N/A
9031667	12/2014	Williams	N/A	N/A
9033973	12/2014	Krapohl et al.	N/A	N/A
9035741	12/2014	Hamel et al.	N/A	N/A
9037259	12/2014	Mathur	N/A	N/A
9039690	12/2014	Kersten et al.	N/A	N/A
9039691	12/2014	Moua et al.	N/A	N/A
9039692	12/2014	Behnke, II et al.	N/A	N/A
9039695	12/2014	Giordano et al.	N/A	N/A
9039696	12/2014	Assmus et al.	N/A	N/A
9039705	12/2014	Takashino	N/A	N/A
9039731	12/2014	Joseph	N/A	N/A
9043018	12/2014	Mohr	N/A	N/A
9044227	12/2014	Shelton, IV et al.	N/A	N/A
9044230	12/2014	Morgan et al.	N/A	N/A
9044238	12/2014	Orszulak	N/A	N/A
9044243	12/2014	Johnson et al.	N/A	N/A
9044245	12/2014	Condie et al.	N/A	N/A
9044256	12/2014	Cadeddu et al.	N/A	N/A
9044261	12/2014	Houser	N/A	N/A
9050083	12/2014	Yates et al.	N/A	N/A
9050093	12/2014	Aldridge et al.	N/A	N/A
9050098	12/2014	Deville et al.	N/A	N/A
9050123	12/2014	Krause et al.	N/A	N/A
9050124	12/2014	Houser	N/A	N/A
9055961	12/2014	Manzo et al.	N/A	N/A
9059547	12/2014	McLawhorn	N/A	N/A
9060770	12/2014	Shelton, IV et al.	N/A	N/A
9060775	12/2014	Wiener et al.	N/A	N/A
9060776	12/2014	Yates et al.	N/A	N/A
9060778	12/2014	Condie et al.	N/A	N/A
9066720	12/2014	Ballakur et al.	N/A	N/A
9066723	12/2014	Beller et al.	N/A	N/A
9066747	12/2014	Robertson	N/A	N/A
9072523	12/2014	Houser et al.	N/A	N/A
9072535	12/2014	Shelton, IV et al.	N/A	N/A
9072536	12/2014	Shelton, IV et al.	N/A	N/A
9072538	12/2014	Suzuki et al.	N/A	N/A
9072539	12/2014	Messerly et al.	N/A	N/A

9084624	12/2014	Larkin et al.	N/A	N/A
9089327	12/2014	Worrell et al.	N/A	N/A
9089360	12/2014	Messerly et al.	N/A	N/A
9095333	12/2014	Konesky et al.	N/A	N/A
9095362	12/2014	Dachs, II et al.	N/A	N/A
9095367	12/2014	Olson et al.	N/A	N/A
9099863	12/2014	Smith et al.	N/A	N/A
9101358	12/2014	Kerr et al.	N/A	N/A
9101385	12/2014	Shelton, IV et al.	N/A	N/A
9107684	12/2014	Ma	N/A	N/A
9107689	12/2014	Robertson et al.	N/A	N/A
9107690	12/2014	Bales, Jr. et al.	N/A	N/A
9113900	12/2014	Buysse et al.	N/A	N/A
9113907	12/2014	Allen, IV et al.	N/A	N/A
9113940	12/2014	Twomey	N/A	N/A
9119657	12/2014	Shelton, IV et al.	N/A	N/A
9119957	12/2014	Gantz et al.	N/A	N/A
9125662	12/2014	Shelton, IV	N/A	N/A
9125667	12/2014	Stone et al.	N/A	N/A
9144453	12/2014	Rencher et al.	N/A	N/A
9147965	12/2014	Lee	N/A	N/A
9149324	12/2014	Huang et al.	N/A	N/A
9149325	12/2014	Worrell et al.	N/A	N/A
9161803	12/2014	Yates et al.	N/A	N/A
9165114	12/2014	Jain et al.	N/A	N/A
9168054	12/2014	Turner et al.	N/A	N/A
9168085	12/2014	Juzkiw et al.	N/A	N/A
9168089	12/2014	Buysse et al.	N/A	N/A
9173656	12/2014	Schurr et al.	N/A	N/A
9179912	12/2014	Yates et al.	N/A	N/A
9186199	12/2014	Strauss et al.	N/A	N/A
9186204	12/2014	Nishimura et al.	N/A	N/A
9186796	12/2014	Ogawa	N/A	N/A
9192380	12/2014	(Tarinelli) Racenet et al.	N/A	N/A
9192421	12/2014	Garrison	N/A	N/A
9192428	12/2014	Houser et al.	N/A	N/A
9192431	12/2014	Woodruff et al.	N/A	N/A
9198714	12/2014	Worrell et al.	N/A	N/A
9198715	12/2014	Livneh	N/A	N/A
9198718	12/2014	Marczyk et al.	N/A	N/A
9198776	12/2014	Young	N/A	N/A
9204879	12/2014	Shelton, IV	N/A	N/A
9204891	12/2014	Weitzman	N/A	N/A
9204918	12/2014	Germain et al.	N/A	N/A
9204923	12/2014	Manzo et al.	N/A	N/A
9216050	12/2014	Condie et al.	N/A	N/A
9216051	12/2014	Fischer et al.	N/A	N/A
9216062	12/2014	Duque et al.	N/A	N/A
9220483	12/2014	Frankhouser et al.	N/A	N/A

9220527	12/2014	Houser et al.	N/A	N/A
9220559	12/2014	Worrell et al.	N/A	N/A
9226750	12/2015	Weir et al.	N/A	N/A
9226751	12/2015	Shelton, IV et al.	N/A	N/A
9226766	12/2015	Aldridge et al.	N/A	N/A
9226767	12/2015	Stulen et al.	N/A	N/A
9232979	12/2015	Parihar et al.	N/A	N/A
9237891	12/2015	Shelton, IV	N/A	N/A
9237921	12/2015	Messerly et al.	N/A	N/A
9241060	12/2015	Fujisaki	N/A	N/A
9241692	12/2015	Gunday et al.	N/A	N/A
9241728	12/2015	Price et al.	N/A	N/A
9241730	12/2015	Babaev	N/A	N/A
9241731	12/2015	Boudreaux et al.	N/A	N/A
9241768	12/2015	Sandhu et al.	N/A	N/A
9247953	12/2015	Palmer et al.	N/A	N/A
9254165	12/2015	Aronow et al.	N/A	N/A
9259234	12/2015	Robertson et al.	N/A	N/A
9259265	12/2015	Harris et al.	N/A	N/A
9265567	12/2015	Orban, III et al.	N/A	N/A
9265926	12/2015	Strobl et al.	N/A	N/A
9265973	12/2015	Akagane	N/A	N/A
9266310	12/2015	Krogdahl et al.	N/A	N/A
9277962	12/2015	Koss et al.	N/A	N/A
9282974	12/2015	Shelton, IV	N/A	N/A
9283027	12/2015	Monson et al.	N/A	N/A
9283045	12/2015	Rhee et al.	N/A	N/A
9283054	12/2015	Morgan et al.	N/A	N/A
9289256	12/2015	Shelton, IV et al.	N/A	N/A
9295514	12/2015	Shelton, IV et al.	N/A	N/A
9301759	12/2015	Spivey et al.	N/A	N/A
9305497	12/2015	Seo et al.	N/A	N/A
9307388	12/2015	Liang et al.	N/A	N/A
9307986	12/2015	Hall et al.	N/A	N/A
9308009	12/2015	Madan et al.	N/A	N/A
9308014	12/2015	Fischer	N/A	N/A
9314261	12/2015	Bales, Jr. et al.	N/A	N/A
9314292	12/2015	Trees et al.	N/A	N/A
9314301	12/2015	Ben-Haim et al.	N/A	N/A
9326754	12/2015	Polster	N/A	N/A
9326767	12/2015	Koch et al.	N/A	N/A
9326787	12/2015	Sanai et al.	N/A	N/A
9326788	12/2015	Batross et al.	N/A	N/A
9332987	12/2015	Leimbach et al.	N/A	N/A
9333025	12/2015	Monson et al.	N/A	N/A
9333034	12/2015	Hancock	N/A	N/A
9339289	12/2015	Robertson	N/A	N/A
9339323	12/2015	Eder et al.	N/A	N/A
9339326	12/2015	McCullagh et al.	N/A	N/A
9345481	12/2015	Hall et al.	N/A	N/A

9345534	12/2015	Artale et al.	N/A	N/A
9345900	12/2015	Wu et al.	N/A	N/A
9351642	12/2015	Nadkarni et al.	N/A	N/A
9351726	12/2015	Leimbach et al.	N/A	N/A
9351727	12/2015	Leimbach et al.	N/A	N/A
9351754	12/2015	Vakharia et al.	N/A	N/A
9352173	12/2015	Yamada et al.	N/A	N/A
9358003	12/2015	Hall et al.	N/A	N/A
9358065	12/2015	Ladtkow et al.	N/A	N/A
9364171	12/2015	Harris et al.	N/A	N/A
9364230	12/2015	Shelton, IV et al.	N/A	N/A
9364279	12/2015	Houser et al.	N/A	N/A
9370364	12/2015	Smith et al.	N/A	N/A
9370400	12/2015	Parihar	N/A	N/A
9370611	12/2015	Ross et al.	N/A	N/A
9375206	12/2015	Vidal et al.	N/A	N/A
9375230	12/2015	Ross et al.	N/A	N/A
9375232	12/2015	Hunt et al.	N/A	N/A
9375256	12/2015	Cunningham et al.	N/A	N/A
9375264	12/2015	Horner et al.	N/A	N/A
9375267	12/2015	Kerr et al.	N/A	N/A
9385831	12/2015	Marr et al.	N/A	N/A
9386983	12/2015	Swensgard et al.	N/A	N/A
9393037	12/2015	Olson et al.	N/A	N/A
9393070	12/2015	Gelfand et al.	N/A	N/A
9398911	12/2015	Auld	N/A	N/A
9402680	12/2015	Ginnebaugh et al.	N/A	N/A
9402682	12/2015	Worrell et al.	N/A	N/A
9408606	12/2015	Shelton, IV	N/A	N/A
9408622	12/2015	Stulen et al.	N/A	N/A
9408660	12/2015	Strobl et al.	N/A	N/A
9414853	12/2015	Stulen et al.	N/A	N/A
9414880	12/2015	Monson et al.	N/A	N/A
9421014	12/2015	Ingmanson et al.	N/A	N/A
9421060	12/2015	Monson et al.	N/A	N/A
9427249	12/2015	Robertson et al.	N/A	N/A
9427279	12/2015	Muniz-Medina et al.	N/A	N/A
9439668	12/2015	Timm et al.	N/A	N/A
9439669	12/2015	Wiener et al.	N/A	N/A
9439671	12/2015	Akagane	N/A	N/A
9442288	12/2015	Tanimura	N/A	N/A
9445784	12/2015	O'Keeffe	N/A	N/A
9445832	12/2015	Wiener et al.	N/A	N/A
9451967	12/2015	Jordan et al.	N/A	N/A
9456863	12/2015	Moua	N/A	N/A
9456864	12/2015	Witt et al.	N/A	N/A
9468438	12/2015	Baber et al.	N/A	N/A
9468498	12/2015	Sigmon, Jr.	N/A	N/A
9474542	12/2015	Slipszenko et al.	N/A	N/A

9474568	12/2015	Akagane	N/A	N/A
9486236	12/2015	Price et al.	N/A	N/A
9492146	12/2015	Kostrzewski et al.	N/A	N/A
9492224	12/2015	Boudreaux et al.	N/A	N/A
9498245	12/2015	Voegele et al.	N/A	N/A
9498275	12/2015	Wham et al.	N/A	N/A
9504483	12/2015	Houser et al.	N/A	N/A
9504520	12/2015	Worrell et al.	N/A	N/A
9504524	12/2015	Behnke, II	N/A	N/A
9504855	12/2015	Messerly et al.	N/A	N/A
9510850	12/2015	Robertson et al.	N/A	N/A
9510906	12/2015	Boudreaux et al.	N/A	N/A
9522029	12/2015	Yates et al.	N/A	N/A
9522032	12/2015	Behnke	N/A	N/A
9526564	12/2015	Rusin	N/A	N/A
9526565	12/2015	Strobl	N/A	N/A
9545253	12/2016	Worrell et al.	N/A	N/A
9545497	12/2016	Wenderow et al.	N/A	N/A
9554465	12/2016	Liu et al.	N/A	N/A
9554794	12/2016	Baber et al.	N/A	N/A
9554846	12/2016	Boudreaux	N/A	N/A
9554854	12/2016	Yates et al.	N/A	N/A
9560995	12/2016	Addison et al.	N/A	N/A
9561038	12/2016	Shelton, IV et al.	N/A	N/A
9572592	12/2016	Price et al.	N/A	N/A
9574644	12/2016	Parihar	N/A	N/A
9585714	12/2016	Livneh	N/A	N/A
9592056	12/2016	Mozdzierz et al.	N/A	N/A
9592072	12/2016	Akagane	N/A	N/A
9597143	12/2016	Madan et al.	N/A	N/A
9603669	12/2016	Govari et al.	N/A	N/A
9610091	12/2016	Johnson et al.	N/A	N/A
9610114	12/2016	Baxter, III et al.	N/A	N/A
9615877	12/2016	Tyrrell et al.	N/A	N/A
9623237	12/2016	Turner et al.	N/A	N/A
9629623	12/2016	Lytle, IV et al.	N/A	N/A
9629629	12/2016	Leimbach et al.	N/A	N/A
9632573	12/2016	Ogawa et al.	N/A	N/A
9636135	12/2016	Stulen	N/A	N/A
9636165	12/2016	Larson et al.	N/A	N/A
9636167	12/2016	Gregg	N/A	N/A
9638770	12/2016	Dietz et al.	N/A	N/A
9642644	12/2016	Houser et al.	N/A	N/A
9642669	12/2016	Takashino et al.	N/A	N/A
9643052	12/2016	Tchao et al.	N/A	N/A
9649110	12/2016	Parihar et al.	N/A	N/A
9649111	12/2016	Shelton, IV et al.	N/A	N/A
9649126	12/2016	Robertson et al.	N/A	N/A
9649173	12/2016	Choi et al.	N/A	N/A
9655670	12/2016	Larson et al.	N/A	N/A

9662131	12/2016	Omori et al.	N/A	N/A
9668806	12/2016	Unger et al.	N/A	N/A
9671860	12/2016	Ogawa et al.	N/A	N/A
9674949	12/2016	Liu et al.	N/A	N/A
9675374	12/2016	Stulen et al.	N/A	N/A
9675375	12/2016	Houser et al.	N/A	N/A
9681884	12/2016	Clem et al.	N/A	N/A
9687230	12/2016	Leimbach et al.	N/A	N/A
9687290	12/2016	Keller	N/A	N/A
9690362	12/2016	Leimbach et al.	N/A	N/A
9693817	12/2016	Mehta et al.	N/A	N/A
9700309	12/2016	Jaworek et al.	N/A	N/A
9700339	12/2016	Nield	N/A	N/A
9700343	12/2016	Messerly et al.	N/A	N/A
9705456	12/2016	Gilbert	N/A	N/A
9707004	12/2016	Houser et al.	N/A	N/A
9707027	12/2016	Ruddenklau et al.	N/A	N/A
9707030	12/2016	Davison et al.	N/A	N/A
9713507	12/2016	Stulen et al.	N/A	N/A
9717548	12/2016	Couture	N/A	N/A
9717552	12/2016	Cosman et al.	N/A	N/A
9724094	12/2016	Baber et al.	N/A	N/A
9724118	12/2016	Schulte et al.	N/A	N/A
9724120	12/2016	Faller et al.	N/A	N/A
9724152	12/2016	Horlle et al.	N/A	N/A
9730695	12/2016	Leimbach et al.	N/A	N/A
9733663	12/2016	Leimbach et al.	N/A	N/A
9737301	12/2016	Baber et al.	N/A	N/A
9737326	12/2016	Worrell et al.	N/A	N/A
9737355	12/2016	Yates et al.	N/A	N/A
9737358	12/2016	Beckman et al.	N/A	N/A
9743929	12/2016	Leimbach et al.	N/A	N/A
9743946	12/2016	Faller et al.	N/A	N/A
9743947	12/2016	Price et al.	N/A	N/A
9750499	12/2016	Leimbach et al.	N/A	N/A
9757128	12/2016	Baber et al.	N/A	N/A
9757142	12/2016	Shimizu	N/A	N/A
9757150	12/2016	Alexander et al.	N/A	N/A
9757186	12/2016	Boudreaux et al.	N/A	N/A
9764164	12/2016	Wiener et al.	N/A	N/A
9770285	12/2016	Zoran et al.	N/A	N/A
9782169	12/2016	Kimsey et al.	N/A	N/A
9782214	12/2016	Houser et al.	N/A	N/A
9788836	12/2016	Overmyer et al.	N/A	N/A
9788851	12/2016	Dannaher et al.	N/A	N/A
9795405	12/2016	Price et al.	N/A	N/A
9795436	12/2016	Yates et al.	N/A	N/A
9795808	12/2016	Messerly et al.	N/A	N/A
9801626	12/2016	Parihar et al.	N/A	N/A
9801648	12/2016	Houser et al.	N/A	N/A

9802033	12/2016	Hibner et al.	N/A	N/A
9804618	12/2016	Leimbach et al.	N/A	N/A
9808244	12/2016	Leimbach et al.	N/A	N/A
9808246	12/2016	Shelton, IV et al.	N/A	N/A
9808308	12/2016	Faller et al.	N/A	N/A
9814460	12/2016	Kimsey et al.	N/A	N/A
9814514	12/2016	Shelton, IV et al.	N/A	N/A
9815211	12/2016	Cao et al.	N/A	N/A
9820738	12/2016	Lytle, IV et al.	N/A	N/A
9820768	12/2016	Gee et al.	N/A	N/A
9820771	12/2016	Norton et al.	N/A	N/A
9820806	12/2016	Lee et al.	N/A	N/A
9826976	12/2016	Parihar et al.	N/A	N/A
9826977	12/2016	Leimbach et al.	N/A	N/A
9839443	12/2016	Brockman et al.	N/A	N/A
9844368	12/2016	Boudreaux et al.	N/A	N/A
9844374	12/2016	Lytle, IV et al.	N/A	N/A
9844375	12/2016	Overmyer et al.	N/A	N/A
9848901	12/2016	Robertson et al.	N/A	N/A
9848902	12/2016	Price et al.	N/A	N/A
9848937	12/2016	Trees et al.	N/A	N/A
9861381	12/2017	Johnson	N/A	N/A
9861428	12/2017	Trees et al.	N/A	N/A
9867612	12/2017	Parihar et al.	N/A	N/A
9867651	12/2017	Wham	N/A	N/A
9867670	12/2017	Brannan et al.	N/A	N/A
9872722	12/2017	Lech	N/A	N/A
9872725	12/2017	Worrell et al.	N/A	N/A
9872726	12/2017	Morisaki	N/A	N/A
9877720	12/2017	Worrell et al.	N/A	N/A
9877776	12/2017	Boudreaux	N/A	N/A
9877782	12/2017	Voegele et al.	N/A	N/A
9878184	12/2017	Beaupre	N/A	N/A
9883860	12/2017	Leimbach	N/A	N/A
9883884	12/2017	Neurohr et al.	N/A	N/A
9888919	12/2017	Leimbach et al.	N/A	N/A
9888958	12/2017	Evans et al.	N/A	N/A
9895148	12/2017	Shelton, IV et al.	N/A	N/A
9895160	12/2017	Fan et al.	N/A	N/A
9901321	12/2017	Harks et al.	N/A	N/A
9901342	12/2017	Shelton, IV et al.	N/A	N/A
9901383	12/2017	Hassler, Jr.	N/A	N/A
9901754	12/2017	Yamada	N/A	N/A
9907563	12/2017	Germain et al.	N/A	N/A
9913642	12/2017	Leimbach et al.	N/A	N/A
9913656	12/2017	Stulen	N/A	N/A
9913680	12/2017	Voegele et al.	N/A	N/A
9918730	12/2017	Trees et al.	N/A	N/A
9924961	12/2017	Shelton, IV et al.	N/A	N/A
9925003	12/2017	Parihar et al.	N/A	N/A

9931118	12/2017	Shelton, IV et al.	N/A	N/A
9937001	12/2017	Nakamura	N/A	N/A
9943309	12/2017	Shelton, IV et al.	N/A	N/A
9949785	12/2017	Price et al.	N/A	N/A
9949788	12/2017	Boudreaux	N/A	N/A
9962182	12/2017	Dietz et al.	N/A	N/A
9968355	12/2017	Shelton, IV et al.	N/A	N/A
9974539	12/2017	Yates et al.	N/A	N/A
9987000	12/2017	Shelton, IV et al.	N/A	N/A
9987033	12/2017	Neurohr et al.	N/A	N/A
9993248	12/2017	Shelton, IV et al.	N/A	N/A
9993258	12/2017	Shelton, IV et al.	N/A	N/A
9993289	12/2017	Sobajima et al.	N/A	N/A
10004497	12/2017	Overmyer et al.	N/A	N/A
10004501	12/2017	Shelton, IV et al.	N/A	N/A
10004526	12/2017	Dycus et al.	N/A	N/A
10004527	12/2017	Gee et al.	N/A	N/A
D822206	12/2017	Shelton, IV et al.	N/A	N/A
10010339	12/2017	Witt et al.	N/A	N/A
10010341	12/2017	Houser et al.	N/A	N/A
10013049	12/2017	Leimbach et al.	N/A	N/A
10016199	12/2017	Baber et al.	N/A	N/A
10016207	12/2017	Suzuki et al.	N/A	N/A
10022142	12/2017	Aranyi et al.	N/A	N/A
10022567	12/2017	Messerly et al.	N/A	N/A
10022568	12/2017	Messerly et al.	N/A	N/A
10028761	12/2017	Leimbach et al.	N/A	N/A
10028786	12/2017	Mucilli et al.	N/A	N/A
10034684	12/2017	Weisenburgh, II et al.	N/A	N/A
10034704	12/2017	Asher et al.	N/A	N/A
D826405	12/2017	Shelton, IV et al.	N/A	N/A
10039588	12/2017	Harper et al.	N/A	N/A
10041822	12/2017	Zemlok	N/A	N/A
10045776	12/2017	Shelton, IV et al.	N/A	N/A
10045779	12/2017	Savage et al.	N/A	N/A
10045794	12/2017	Witt et al.	N/A	N/A
10045810	12/2017	Schall et al.	N/A	N/A
10045819	12/2017	Jensen et al.	N/A	N/A
10052044	12/2017	Shelton, IV et al.	N/A	N/A
10052102	12/2017	Baxter, III et al.	N/A	N/A
10070916	12/2017	Artale	N/A	N/A
10080609	12/2017	Hancock et al.	N/A	N/A
10085748	12/2017	Morgan et al.	N/A	N/A
10085762	12/2017	Timm et al.	N/A	N/A
10085792	12/2017	Johnson et al.	N/A	N/A
10092310	12/2017	Boudreaux et al.	N/A	N/A
10092344	12/2017	Mohr et al.	N/A	N/A
10092347	12/2017	Weissaupt et al.	N/A	N/A
10092348	12/2017	Boudreaux	N/A	N/A

10092350	12/2017	Rothweiler et al.	N/A	N/A
10105140	12/2017	Malinouskas et al.	N/A	N/A
10111679	12/2017	Baber et al.	N/A	N/A
10111699	12/2017	Boudreaux	N/A	N/A
10111703	12/2017	Cosman, Jr. et al.	N/A	N/A
10117649	12/2017	Baxter et al.	N/A	N/A
10117667	12/2017	Robertson et al.	N/A	N/A
10117702	12/2017	Danziger et al.	N/A	N/A
10123835	12/2017	Keller et al.	N/A	N/A
10130367	12/2017	Cappola et al.	N/A	N/A
10130410	12/2017	Strobl et al.	N/A	N/A
10130412	12/2017	Wham	N/A	N/A
10135242	12/2017	Baber et al.	N/A	N/A
10136887	12/2017	Shelton, IV et al.	N/A	N/A
10149680	12/2017	Parihar et al.	N/A	N/A
10154848	12/2017	Chernov et al.	N/A	N/A
10154852	12/2017	Conlon et al.	N/A	N/A
10159483	12/2017	Beckman et al.	N/A	N/A
10159524	12/2017	Yates et al.	N/A	N/A
10166060	12/2018	Johnson et al.	N/A	N/A
10172665	12/2018	Heckel et al.	N/A	N/A
10172669	12/2018	Felder et al.	N/A	N/A
10178992	12/2018	Wise et al.	N/A	N/A
10179022	12/2018	Yates et al.	N/A	N/A
10180463	12/2018	Beckman et al.	N/A	N/A
10182816	12/2018	Shelton, IV et al.	N/A	N/A
10182818	12/2018	Hensel et al.	N/A	N/A
10188385	12/2018	Kerr et al.	N/A	N/A
10188455	12/2018	Hancock et al.	N/A	N/A
10194907	12/2018	Marczyk et al.	N/A	N/A
10194972	12/2018	Yates et al.	N/A	N/A
10194973	12/2018	Wiener et al.	N/A	N/A
10194976	12/2018	Boudreaux	N/A	N/A
10194977	12/2018	Yang	N/A	N/A
10194999	12/2018	Bacher et al.	N/A	N/A
10201364	12/2018	Leimbach et al.	N/A	N/A
10201365	12/2018	Boudreaux et al.	N/A	N/A
10201382	12/2018	Wiener et al.	N/A	N/A
10206676	12/2018	Shelton, IV	N/A	N/A
10226250	12/2018	Beckman et al.	N/A	N/A
10226273	12/2018	Messerly et al.	N/A	N/A
10231747	12/2018	Stulen et al.	N/A	N/A
10238385	12/2018	Yates et al.	N/A	N/A
10238391	12/2018	Leimbach et al.	N/A	N/A
10245027	12/2018	Shelton, IV et al.	N/A	N/A
10245028	12/2018	Shelton, IV et al.	N/A	N/A
10245029	12/2018	Hunter et al.	N/A	N/A
10245030	12/2018	Hunter et al.	N/A	N/A
10245033	12/2018	Overmyer et al.	N/A	N/A
10245095	12/2018	Boudreaux	N/A	N/A

10245097	12/2018	Honda et al.	N/A	N/A
10245104	12/2018	McKenna et al.	N/A	N/A
10251664	12/2018	Shelton, IV et al.	N/A	N/A
10258331	12/2018	Shelton, IV et al.	N/A	N/A
10258505	12/2018	Ovchinnikov	N/A	N/A
10263171	12/2018	Wiener et al.	N/A	N/A
10265068	12/2018	Harris et al.	N/A	N/A
10265117	12/2018	Wiener et al.	N/A	N/A
10265118	12/2018	Gerhardt	N/A	N/A
10271840	12/2018	Sapre	N/A	N/A
10271851	12/2018	Shelton, IV et al.	N/A	N/A
D847989	12/2018	Shelton, IV et al.	N/A	N/A
10278721	12/2018	Dietz et al.	N/A	N/A
10285705	12/2018	Shelton, IV et al.	N/A	N/A
10285724	12/2018	Faller et al.	N/A	N/A
10285750	12/2018	Coulson et al.	N/A	N/A
10292704	12/2018	Harris et al.	N/A	N/A
10299810	12/2018	Robertson et al.	N/A	N/A
10299821	12/2018	Shelton, IV et al.	N/A	N/A
D850617	12/2018	Shelton, IV et al.	N/A	N/A
D851762	12/2018	Shelton, IV et al.	N/A	N/A
10307159	12/2018	Harris et al.	N/A	N/A
10314579	12/2018	Chowaniec et al.	N/A	N/A
10314582	12/2018	Shelton, IV et al.	N/A	N/A
10314638	12/2018	Gee et al.	N/A	N/A
10321907	12/2018	Shelton, IV et al.	N/A	N/A
10321950	12/2018	Yates et al.	N/A	N/A
D854151	12/2018	Shelton, IV et al.	N/A	N/A
10335149	12/2018	Baxter, III et al.	N/A	N/A
10335182	12/2018	Stulen et al.	N/A	N/A
10335183	12/2018	Worrell et al.	N/A	N/A
10335614	12/2018	Messerly et al.	N/A	N/A
10342543	12/2018	Shelton, IV et al.	N/A	N/A
10342602	12/2018	Strobl et al.	N/A	N/A
10342606	12/2018	Cosman et al.	N/A	N/A
10342623	12/2018	Huelman et al.	N/A	N/A
10348941	12/2018	Elliot, Jr. et al.	N/A	N/A
10349999	12/2018	Yates et al.	N/A	N/A
10350016	12/2018	Burbank et al.	N/A	N/A
10350025	12/2018	Loyd et al.	N/A	N/A
10357246	12/2018	Shelton, IV et al.	N/A	N/A
10357247	12/2018	Shelton, IV et al.	N/A	N/A
10357303	12/2018	Conlon et al.	N/A	N/A
10363084	12/2018	Friedrichs	N/A	N/A
10368861	12/2018	Baxter, III et al.	N/A	N/A
10368865	12/2018	Harris et al.	N/A	N/A
10376263	12/2018	Morgan et al.	N/A	N/A
10376305	12/2018	Yates et al.	N/A	N/A
10390841	12/2018	Shelton, IV et al.	N/A	N/A
10398439	12/2018	Cabrera et al.	N/A	N/A

10398466	12/2018	Stulen et al.	N/A	N/A
10398497	12/2018	Batross et al.	N/A	N/A
10405857	12/2018	Shelton, IV et al.	N/A	N/A
10405863	12/2018	Wise et al.	N/A	N/A
10413291	12/2018	Worthington et al.	N/A	N/A
10413293	12/2018	Shelton, IV et al.	N/A	N/A
10413297	12/2018	Harris et al.	N/A	N/A
10413352	12/2018	Thomas et al.	N/A	N/A
10413353	12/2018	Kerr et al.	N/A	N/A
10420552	12/2018	Shelton, IV et al.	N/A	N/A
10420579	12/2018	Wiener et al.	N/A	N/A
10420607	12/2018	Woloszko et al.	N/A	N/A
D865175	12/2018	Widenhouse et al.	N/A	N/A
10426471	12/2018	Shelton, IV et al.	N/A	N/A
10426507	12/2018	Wiener et al.	N/A	N/A
10426546	12/2018	Graham et al.	N/A	N/A
10426978	12/2018	Akagane	N/A	N/A
10433837	12/2018	Worthington et al.	N/A	N/A
10433849	12/2018	Shelton, IV et al.	N/A	N/A
10433865	12/2018	Witt et al.	N/A	N/A
10433866	12/2018	Witt et al.	N/A	N/A
10433900	12/2018	Harris et al.	N/A	N/A
10441279	12/2018	Shelton, IV et al.	N/A	N/A
10441308	12/2018	Robertson	N/A	N/A
10441310	12/2018	Olson et al.	N/A	N/A
10441345	12/2018	Aldridge et al.	N/A	N/A
10448948	12/2018	Shelton, IV et al.	N/A	N/A
10448950	12/2018	Shelton, IV et al.	N/A	N/A
10448986	12/2018	Zikorus et al.	N/A	N/A
10456140	12/2018	Shelton, IV et al.	N/A	N/A
10456193	12/2018	Yates et al.	N/A	N/A
10463421	12/2018	Boudreaux et al.	N/A	N/A
10463887	12/2018	Witt et al.	N/A	N/A
10470762	12/2018	Leimbach et al.	N/A	N/A
10470764	12/2018	Baxter, III et al.	N/A	N/A
10478182	12/2018	Taylor	N/A	N/A
10478190	12/2018	Miller et al.	N/A	N/A
10485542	12/2018	Shelton, IV et al.	N/A	N/A
10485543	12/2018	Shelton, IV et al.	N/A	N/A
10485607	12/2018	Strobl et al.	N/A	N/A
D869655	12/2018	Shelton, IV et al.	N/A	N/A
10492785	12/2018	Overmyer et al.	N/A	N/A
10492849	12/2018	Juergens et al.	N/A	N/A
10499914	12/2018	Huang et al.	N/A	N/A
10507033	12/2018	Dickerson et al.	N/A	N/A
10512795	12/2018	Voegele et al.	N/A	N/A
10517595	12/2018	Hunter et al.	N/A	N/A
10517596	12/2018	Hunter et al.	N/A	N/A
10517627	12/2018	Timm et al.	N/A	N/A
10524787	12/2019	Shelton, IV et al.	N/A	N/A

10524789	12/2019	Swayze et al.	N/A	N/A
10524854	12/2019	Woodruff et al.	N/A	N/A
10524872	12/2019	Stewart et al.	N/A	N/A
10531874	12/2019	Morgan et al.	N/A	N/A
10537324	12/2019	Shelton, IV et al.	N/A	N/A
10537325	12/2019	Bakos et al.	N/A	N/A
10537351	12/2019	Shelton, IV et al.	N/A	N/A
10542979	12/2019	Shelton, IV et al.	N/A	N/A
10542982	12/2019	Beckman et al.	N/A	N/A
10542991	12/2019	Shelton, IV et al.	N/A	N/A
10543008	12/2019	Vakharia et al.	N/A	N/A
10548504	12/2019	Shelton, IV et al.	N/A	N/A
10548655	12/2019	Scheib et al.	N/A	N/A
10555769	12/2019	Worrell et al.	N/A	N/A
10561560	12/2019	Boutoussov et al.	N/A	N/A
10568624	12/2019	Shelton, IV et al.	N/A	N/A
10568625	12/2019	Harris et al.	N/A	N/A
10568626	12/2019	Shelton, IV et al.	N/A	N/A
10568632	12/2019	Miller et al.	N/A	N/A
10575892	12/2019	Danziger et al.	N/A	N/A
10582928	12/2019	Hunter et al.	N/A	N/A
10588625	12/2019	Weaner et al.	N/A	N/A
10588630	12/2019	Shelton, IV et al.	N/A	N/A
10588631	12/2019	Shelton, IV et al.	N/A	N/A
10588632	12/2019	Shelton, IV et al.	N/A	N/A
10588633	12/2019	Shelton, IV et al.	N/A	N/A
10595929	12/2019	Boudreaux et al.	N/A	N/A
10595930	12/2019	Scheib et al.	N/A	N/A
10603036	12/2019	Hunter et al.	N/A	N/A
10610224	12/2019	Shelton, IV et al.	N/A	N/A
10610286	12/2019	Wiener et al.	N/A	N/A
10610313	12/2019	Bailey et al.	N/A	N/A
10617412	12/2019	Shelton, IV et al.	N/A	N/A
10617420	12/2019	Shelton, IV et al.	N/A	N/A
10617464	12/2019	Duppuis	N/A	N/A
10624635	12/2019	Harris et al.	N/A	N/A
10624691	12/2019	Wiener et al.	N/A	N/A
10631858	12/2019	Burbank	N/A	N/A
10631859	12/2019	Shelton, IV et al.	N/A	N/A
10631928	12/2019	Basu et al.	N/A	N/A
10632630	12/2019	Cao et al.	N/A	N/A
RE47996	12/2019	Turner et al.	N/A	N/A
10639034	12/2019	Harris et al.	N/A	N/A
10639035	12/2019	Shelton, IV et al.	N/A	N/A
10639037	12/2019	Shelton, IV et al.	N/A	N/A
10639092	12/2019	Corbett et al.	N/A	N/A
10639098	12/2019	Cosman et al.	N/A	N/A
10646269	12/2019	Worrell et al.	N/A	N/A
10646292	12/2019	Solomon et al.	N/A	N/A
10653413	12/2019	Worthington et al.	N/A	N/A

10660692	12/2019	Lesko et al.	N/A	N/A
10667809	12/2019	Bakos et al.	N/A	N/A
10667810	12/2019	Shelton, IV et al.	N/A	N/A
10667811	12/2019	Harris et al.	N/A	N/A
10675021	12/2019	Harris et al.	N/A	N/A
10675024	12/2019	Shelton, IV et al.	N/A	N/A
10675025	12/2019	Swayze et al.	N/A	N/A
10675026	12/2019	Harris et al.	N/A	N/A
10677764	12/2019	Ross et al.	N/A	N/A
10682136	12/2019	Harris et al.	N/A	N/A
10682138	12/2019	Shelton, IV et al.	N/A	N/A
10687806	12/2019	Shelton, IV et al.	N/A	N/A
10687809	12/2019	Shelton, IV et al.	N/A	N/A
10687810	12/2019	Shelton, IV et al.	N/A	N/A
10687884	12/2019	Wiener et al.	N/A	N/A
10688321	12/2019	Wiener et al.	N/A	N/A
10695055	12/2019	Shelton, IV et al.	N/A	N/A
10695057	12/2019	Shelton, IV et al.	N/A	N/A
10695058	12/2019	Lytle, IV et al.	N/A	N/A
10695119	12/2019	Smith	N/A	N/A
10702270	12/2019	Shelton, IV et al.	N/A	N/A
10702329	12/2019	Strobl et al.	N/A	N/A
10709446	12/2019	Harris et al.	N/A	N/A
10709469	12/2019	Shelton, IV et al.	N/A	N/A
10709906	12/2019	Nield	N/A	N/A
10716615	12/2019	Shelton, IV et al.	N/A	N/A
10722233	12/2019	Wellman	N/A	N/A
D893717	12/2019	Messerly et al.	N/A	N/A
10729458	12/2019	Stoddard et al.	N/A	N/A
10729494	12/2019	Parihar et al.	N/A	N/A
10736629	12/2019	Shelton, IV et al.	N/A	N/A
10736685	12/2019	Wiener et al.	N/A	N/A
10751108	12/2019	Yates et al.	N/A	N/A
10751138	12/2019	Giordano et al.	N/A	N/A
10758229	12/2019	Shelton, IV et al.	N/A	N/A
10758230	12/2019	Shelton, IV et al.	N/A	N/A
10758232	12/2019	Shelton, IV et al.	N/A	N/A
10758294	12/2019	Jones	N/A	N/A
10765427	12/2019	Shelton, IV et al.	N/A	N/A
10765470	12/2019	Yates et al.	N/A	N/A
10772629	12/2019	Shelton, IV et al.	N/A	N/A
10772630	12/2019	Wixey	N/A	N/A
10779821	12/2019	Harris et al.	N/A	N/A
10779823	12/2019	Shelton, IV et al.	N/A	N/A
10779824	12/2019	Shelton, IV et al.	N/A	N/A
10779825	12/2019	Shelton, IV et al.	N/A	N/A
10779845	12/2019	Timm et al.	N/A	N/A
10779849	12/2019	Shelton, IV et al.	N/A	N/A
10779879	12/2019	Yates et al.	N/A	N/A
10786253	12/2019	Shelton, IV et al.	N/A	N/A

10786276	12/2019	Hirai et al.	N/A	N/A
10806454	12/2019	Kopp	N/A	N/A
10813638	12/2019	Shelton, IV et al.	N/A	N/A
10820938	12/2019	Fischer et al.	N/A	N/A
10828032	12/2019	Leimbach et al.	N/A	N/A
10828058	12/2019	Shelton, IV et al.	N/A	N/A
10835245	12/2019	Swayze et al.	N/A	N/A
10835246	12/2019	Shelton, IV et al.	N/A	N/A
10835247	12/2019	Shelton, IV et al.	N/A	N/A
10835307	12/2019	Shelton, IV et al.	N/A	N/A
10842492	12/2019	Shelton, IV et al.	N/A	N/A
10842523	12/2019	Shelton, IV et al.	N/A	N/A
10842563	12/2019	Gilbert et al.	N/A	N/A
D906355	12/2019	Messerly et al.	N/A	N/A
10856867	12/2019	Shelton, IV et al.	N/A	N/A
10856868	12/2019	Shelton, IV et al.	N/A	N/A
10856869	12/2019	Shelton, IV et al.	N/A	N/A
10856870	12/2019	Harris et al.	N/A	N/A
10856896	12/2019	Eichmann et al.	N/A	N/A
10856929	12/2019	Yates et al.	N/A	N/A
10856934	12/2019	Trees et al.	N/A	N/A
10874465	12/2019	Weir et al.	N/A	N/A
D908216	12/2020	Messerly et al.	N/A	N/A
10881399	12/2020	Shelton, IV et al.	N/A	N/A
10881401	12/2020	Baber et al.	N/A	N/A
10881409	12/2020	Cabrera	N/A	N/A
10881449	12/2020	Boudreaux et al.	N/A	N/A
10888322	12/2020	Morgan et al.	N/A	N/A
10888347	12/2020	Witt et al.	N/A	N/A
10893863	12/2020	Shelton, IV et al.	N/A	N/A
10893864	12/2020	Harris et al.	N/A	N/A
10893883	12/2020	Dannaher	N/A	N/A
10898186	12/2020	Bakos et al.	N/A	N/A
10898256	12/2020	Yates et al.	N/A	N/A
10912559	12/2020	Harris et al.	N/A	N/A
10912580	12/2020	Green et al.	N/A	N/A
10912603	12/2020	Boudreaux et al.	N/A	N/A
10918385	12/2020	Overmyer et al.	N/A	N/A
10925659	12/2020	Shelton, IV et al.	N/A	N/A
10926022	12/2020	Hickey et al.	N/A	N/A
D914878	12/2020	Shelton, IV et al.	N/A	N/A
10932766	12/2020	Tesar et al.	N/A	N/A
10932847	12/2020	Yates et al.	N/A	N/A
10945727	12/2020	Shelton, IV et al.	N/A	N/A
10952788	12/2020	Asher et al.	N/A	N/A
10959727	12/2020	Hunter et al.	N/A	N/A
10966741	12/2020	Illizaliturri-Sanchez et al.	N/A	N/A
10966747	12/2020	Worrell et al.	N/A	N/A
10973516	12/2020	Shelton, IV et al.	N/A	N/A

10973517	12/2020	Wixey	N/A	N/A
10973520	12/2020	Shelton, IV et al.	N/A	N/A
10980536	12/2020	Weaner et al.	N/A	N/A
10987105	12/2020	Cappola et al.	N/A	N/A
10987123	12/2020	Weir et al.	N/A	N/A
10987156	12/2020	Trees et al.	N/A	N/A
10993715	12/2020	Shelton, IV et al.	N/A	N/A
10993716	12/2020	Shelton, IV et al.	N/A	N/A
10993763	12/2020	Batross et al.	N/A	N/A
11000278	12/2020	Shelton, IV et al.	N/A	N/A
11000279	12/2020	Shelton, IV et al.	N/A	N/A
11020114	12/2020	Shelton, IV et al.	N/A	N/A
11020140	12/2020	Gee et al.	N/A	N/A
11033322	12/2020	Wiener et al.	N/A	N/A
11039834	12/2020	Harris et al.	N/A	N/A
11045191	12/2020	Shelton, IV et al.	N/A	N/A
11045192	12/2020	Harris et al.	N/A	N/A
11045275	12/2020	Boudreaux et al.	N/A	N/A
11051840	12/2020	Shelton, IV et al.	N/A	N/A
11051873	12/2020	Wiener et al.	N/A	N/A
11058424	12/2020	Shelton, IV et al.	N/A	N/A
11058447	12/2020	Houser	N/A	N/A
11058448	12/2020	Shelton, IV et al.	N/A	N/A
11058475	12/2020	Wiener et al.	N/A	N/A
11064997	12/2020	Shelton, IV et al.	N/A	N/A
11065048	12/2020	Messerly et al.	N/A	N/A
11083455	12/2020	Shelton, IV et al.	N/A	N/A
11083458	12/2020	Harris et al.	N/A	N/A
11090048	12/2020	Fanelli et al.	N/A	N/A
11090049	12/2020	Bakos et al.	N/A	N/A
11090104	12/2020	Wiener et al.	N/A	N/A
11096688	12/2020	Shelton, IV et al.	N/A	N/A
11096752	12/2020	Stulen et al.	N/A	N/A
11109866	12/2020	Shelton, IV et al.	N/A	N/A
11129611	12/2020	Shelton, IV et al.	N/A	N/A
11129666	12/2020	Messerly et al.	N/A	N/A
11129669	12/2020	Stulen et al.	N/A	N/A
11129670	12/2020	Shelton, IV et al.	N/A	N/A
11134942	12/2020	Harris et al.	N/A	N/A
11134978	12/2020	Shelton, IV et al.	N/A	N/A
11141154	12/2020	Shelton, IV et al.	N/A	N/A
11141213	12/2020	Yates et al.	N/A	N/A
11147551	12/2020	Shelton, IV	N/A	N/A
11147553	12/2020	Shelton, IV	N/A	N/A
11160551	12/2020	Shelton, IV et al.	N/A	N/A
11166716	12/2020	Shelton, IV et al.	N/A	N/A
11172929	12/2020	Shelton, IV	N/A	N/A
11179155	12/2020	Shelton, IV et al.	N/A	N/A
11179173	12/2020	Price et al.	N/A	N/A
11191539	12/2020	Overmyer et al.	N/A	N/A

11191540	12/2020	Aronhalt et al.	N/A	N/A
11197668	12/2020	Shelton, IV et al.	N/A	N/A
11202670	12/2020	Worrell et al.	N/A	N/A
11207065	12/2020	Harris et al.	N/A	N/A
11207067	12/2020	Shelton, IV et al.	N/A	N/A
11213293	12/2021	Worthington et al.	N/A	N/A
11213294	12/2021	Shelton, IV et al.	N/A	N/A
11219453	12/2021	Shelton, IV et al.	N/A	N/A
11224426	12/2021	Shelton, IV et al.	N/A	N/A
11224497	12/2021	Shelton, IV et al.	N/A	N/A
11229437	12/2021	Shelton, IV et al.	N/A	N/A
11229450	12/2021	Shelton, IV et al.	N/A	N/A
11229471	12/2021	Shelton, IV et al.	N/A	N/A
11229472	12/2021	Shelton, IV et al.	N/A	N/A
11234698	12/2021	Shelton, IV et al.	N/A	N/A
11241235	12/2021	Shelton, IV et al.	N/A	N/A
11246592	12/2021	Shelton, IV et al.	N/A	N/A
11246625	12/2021	Kane et al.	N/A	N/A
11246678	12/2021	Shelton, IV et al.	N/A	N/A
11253256	12/2021	Harris et al.	N/A	N/A
11259803	12/2021	Shelton, IV et al.	N/A	N/A
11259805	12/2021	Shelton, IV et al.	N/A	N/A
11259806	12/2021	Shelton, IV et al.	N/A	N/A
11259807	12/2021	Shelton, IV et al.	N/A	N/A
11266405	12/2021	Shelton, IV et al.	N/A	N/A
11266430	12/2021	Clauda et al.	N/A	N/A
11272931	12/2021	Boudreaux et al.	N/A	N/A
11278280	12/2021	Shelton, IV et al.	N/A	N/A
11284890	12/2021	Nalagatla et al.	N/A	N/A
11291440	12/2021	Harris et al.	N/A	N/A
11291444	12/2021	Boudreaux et al.	N/A	N/A
11291445	12/2021	Shelton, IV et al.	N/A	N/A
11291447	12/2021	Shelton, IV et al.	N/A	N/A
11291451	12/2021	Shelton, IV	N/A	N/A
11298127	12/2021	Shelton, IV	N/A	N/A
11298129	12/2021	Bakos et al.	N/A	N/A
11298130	12/2021	Bakos et al.	N/A	N/A
11311342	12/2021	Parihar et al.	N/A	N/A
D950728	12/2021	Bakos et al.	N/A	N/A
D952144	12/2021	Boudreaux	N/A	N/A
11406386	12/2021	Baber et al.	N/A	N/A
D964564	12/2021	Boudreaux	N/A	N/A
11497547	12/2021	McKenna et al.	N/A	N/A
11653920	12/2022	Shelton, IV et al.	N/A	N/A
2001/0025173	12/2000	Ritchie et al.	N/A	N/A
2001/0025183	12/2000	Shahidi	N/A	N/A
2001/0025184	12/2000	Messerly	N/A	N/A
2001/0031950	12/2000	Ryan	N/A	N/A
2001/0039419	12/2000	Francischelli et al.	N/A	N/A
2002/0002377	12/2001	Cimino	N/A	N/A

2002/0002380	12/2001	Bishop	N/A	N/A
2002/0019649	12/2001	Sikora et al.	N/A	N/A
2002/0022836	12/2001	Goble et al.	N/A	N/A
2002/0029036	12/2001	Goble et al.	N/A	N/A
2002/0029055	12/2001	Bonutti	N/A	N/A
2002/0032452	12/2001	Tierney et al.	N/A	N/A
2002/0049551	12/2001	Friedman et al.	N/A	N/A
2002/0052617	12/2001	Anis et al.	N/A	N/A
2002/0077550	12/2001	Rabiner et al.	N/A	N/A
2002/0107517	12/2001	Witt et al.	N/A	N/A
2002/0123749	12/2001	Jain	606/41	A61B 18/1492
2002/0133152	12/2001	Strul	N/A	N/A
2002/0151884	12/2001	Hoey et al.	N/A	N/A
2002/0156466	12/2001	Sakurai et al.	N/A	N/A
2002/0156493	12/2001	Houser et al.	N/A	N/A
2002/0165577	12/2001	Witt et al.	N/A	N/A
2002/0177373	12/2001	Shibata et al.	N/A	N/A
2002/0177862	12/2001	Aranyi et al.	N/A	N/A
2003/0009164	12/2002	Woloszko et al.	N/A	N/A
2003/0014053	12/2002	Nguyen et al.	N/A	N/A
2003/0014087	12/2002	Fang et al.	N/A	N/A
2003/0036705	12/2002	Hare et al.	N/A	N/A
2003/0040758	12/2002	Wang et al.	N/A	N/A
2003/0050572	12/2002	Brautigam et al.	N/A	N/A
2003/0055443	12/2002	Spotnitz	N/A	N/A
2003/0073981	12/2002	Whitman et al.	N/A	N/A
2003/0109778	12/2002	Rashidi	N/A	N/A
2003/0109875	12/2002	Tetzlaff et al.	N/A	N/A
2003/0114851	12/2002	Truckai et al.	N/A	N/A
2003/0130693	12/2002	Levin et al.	N/A	N/A
2003/0139741	12/2002	Goble et al.	N/A	N/A
2003/0144680	12/2002	Kellogg et al.	N/A	N/A
2003/0158548	12/2002	Phan et al.	N/A	N/A
2003/0171747	12/2002	Kanehira et al.	N/A	N/A
2003/0176778	12/2002	Messing et al.	N/A	N/A
2003/0181898	12/2002	Bowers	N/A	N/A
2003/0199794	12/2002	Sakurai et al.	N/A	N/A
2003/0204199	12/2002	Novak et al.	N/A	N/A
2003/0208186	12/2002	Moreyra	N/A	N/A
2003/0212332	12/2002	Fenton et al.	N/A	N/A
2003/0212363	12/2002	Shipp	N/A	N/A
2003/0212392	12/2002	Fenton et al.	N/A	N/A
2003/0212422	12/2002	Fenton et al.	N/A	N/A
2003/0225332	12/2002	Okada et al.	N/A	N/A
2003/0229344	12/2002	Dycus et al.	N/A	N/A
2004/0030254	12/2003	Babaev	N/A	N/A
2004/0030330	12/2003	Brassell et al.	N/A	N/A
2004/0047485	12/2003	Sherrit et al.	N/A	N/A
2004/0054364	12/2003	Aranyi et al.	N/A	N/A

2004/0064151	12/2003	Mollenauer	N/A	N/A
2004/0087943	12/2003	Dycus et al.	N/A	N/A
2004/0092921	12/2003	Kadziauskas et al.	N/A	N/A
2004/0092992	12/2003	Adams et al.	N/A	N/A
2004/0094597	12/2003	Whitman et al.	N/A	N/A
2004/0097911	12/2003	Murakami et al.	N/A	N/A
2004/0097912	12/2003	Gonnering	N/A	N/A
2004/0097919	12/2003	Wellman et al.	N/A	N/A
2004/0097996	12/2003	Rabiner et al.	N/A	N/A
2004/0116952	12/2003	Sakurai et al.	N/A	N/A
2004/0122423	12/2003	Dycus et al.	N/A	N/A
2004/0132383	12/2003	Langford et al.	N/A	N/A
2004/0138621	12/2003	Jahns et al.	N/A	N/A
2004/0142667	12/2003	Lochhead et al.	N/A	N/A
2004/0143263	12/2003	Schechter et al.	N/A	N/A
2004/0147934	12/2003	Kiester	N/A	N/A
2004/0147945	12/2003	Fritzscht	N/A	N/A
2004/0158237	12/2003	Abboud et al.	N/A	N/A
2004/0167508	12/2003	Wham et al.	N/A	N/A
2004/0176686	12/2003	Hare et al.	N/A	N/A
2004/0176751	12/2003	Weitzner et al.	N/A	N/A
2004/0181242	12/2003	Stack et al.	N/A	N/A
2004/0193150	12/2003	Sharkey et al.	N/A	N/A
2004/0193153	12/2003	Sartor et al.	N/A	N/A
2004/0193212	12/2003	Taniguchi et al.	N/A	N/A
2004/0199193	12/2003	Hayashi et al.	N/A	N/A
2004/0215132	12/2003	Yoon	N/A	N/A
2004/0243147	12/2003	Lipow	N/A	N/A
2004/0249374	12/2003	Tetzlaff et al.	N/A	N/A
2004/0260273	12/2003	Wan	N/A	N/A
2004/0260300	12/2003	Gorensek et al.	N/A	N/A
2004/0267311	12/2003	Viola et al.	N/A	N/A
2005/0015125	12/2004	Mioduski et al.	N/A	N/A
2005/0020967	12/2004	Ono	N/A	N/A
2005/0021018	12/2004	Anderson et al.	N/A	N/A
2005/0021065	12/2004	Yamada et al.	N/A	N/A
2005/0021078	12/2004	Vleugels et al.	N/A	N/A
2005/0033278	12/2004	McClurken et al.	N/A	N/A
2005/0033337	12/2004	Muir et al.	N/A	N/A
2005/0070800	12/2004	Takahashi	N/A	N/A
2005/0080427	12/2004	Govari et al.	N/A	N/A
2005/0088285	12/2004	Jei	N/A	N/A
2005/0090817	12/2004	Phan	N/A	N/A
2005/0096683	12/2004	Ellins et al.	N/A	N/A
2005/0099824	12/2004	Dowling et al.	N/A	N/A
2005/0107777	12/2004	West et al.	N/A	N/A
2005/0131390	12/2004	Heinrich et al.	N/A	N/A
2005/0143769	12/2004	White et al.	N/A	N/A
2005/0149108	12/2004	Cox	N/A	N/A
2005/0165429	12/2004	Douglas et al.	N/A	N/A

2005/0171522	12/2004	Christopherson	N/A	N/A
2005/0171533	12/2004	Latterell et al.	N/A	N/A
2005/0177184	12/2004	Easley	N/A	N/A
2005/0182339	12/2004	Lee et al.	N/A	N/A
2005/0187576	12/2004	Whitman et al.	N/A	N/A
2005/0188743	12/2004	Land	N/A	N/A
2005/0192610	12/2004	Houser et al.	N/A	N/A
2005/0192611	12/2004	Houser	N/A	N/A
2005/0206583	12/2004	Lemelson et al.	N/A	N/A
2005/0222598	12/2004	Ho et al.	N/A	N/A
2005/0234484	12/2004	Houser et al.	N/A	N/A
2005/0249667	12/2004	Tuszynski et al.	N/A	N/A
2005/0256405	12/2004	Makin et al.	N/A	N/A
2005/0261588	12/2004	Makin et al.	N/A	N/A
2005/0262175	12/2004	Iino et al.	N/A	N/A
2005/0267464	12/2004	Truckai et al.	N/A	N/A
2005/0271807	12/2004	Iljima et al.	N/A	N/A
2005/0273090	12/2004	Nieman et al.	N/A	N/A
2005/0288659	12/2004	Kimura et al.	N/A	N/A
2006/0025757	12/2005	Heim	N/A	N/A
2006/0030797	12/2005	Zhou et al.	N/A	N/A
2006/0030848	12/2005	Craig et al.	N/A	N/A
2006/0058825	12/2005	Ogura et al.	N/A	N/A
2006/0063130	12/2005	Hayman et al.	N/A	N/A
2006/0064086	12/2005	Odom	N/A	N/A
2006/0066181	12/2005	Bromfield et al.	N/A	N/A
2006/0074442	12/2005	Noriega et al.	N/A	N/A
2006/0079874	12/2005	Faller et al.	N/A	N/A
2006/0079879	12/2005	Faller et al.	N/A	N/A
2006/0095046	12/2005	Trieu et al.	N/A	N/A
2006/0109061	12/2005	Dobson et al.	N/A	N/A
2006/0142656	12/2005	Malackowski et al.	N/A	N/A
2006/0159731	12/2005	Shoshan	N/A	N/A
2006/0190034	12/2005	Nishizawa et al.	N/A	N/A
2006/0206100	12/2005	Eskridge et al.	N/A	N/A
2006/0206115	12/2005	Schomer et al.	N/A	N/A
2006/0211943	12/2005	Beaupre	N/A	N/A
2006/0217700	12/2005	Garito et al.	N/A	N/A
2006/0217729	12/2005	Eskridge et al.	N/A	N/A
2006/0224160	12/2005	Trieu et al.	N/A	N/A
2006/0247558	12/2005	Yamada	N/A	N/A
2006/0253050	12/2005	Yoshimine et al.	N/A	N/A
2006/0259026	12/2005	Godara et al.	N/A	N/A
2006/0259102	12/2005	Slatkine	N/A	N/A
2006/0264809	12/2005	Hansmann et al.	N/A	N/A
2006/0264995	12/2005	Fanton et al.	N/A	N/A
2006/0265035	12/2005	Yachi et al.	N/A	N/A
2006/0270916	12/2005	Skwarek et al.	N/A	N/A
2006/0271030	12/2005	Francis et al.	N/A	N/A
2006/0293656	12/2005	Shadduck et al.	N/A	N/A

2007/0016235	12/2006	Tanaka et al.	N/A	N/A
2007/0016236	12/2006	Beaupre	N/A	N/A
2007/0021738	12/2006	Hasser et al.	N/A	N/A
2007/0027468	12/2006	Wales et al.	N/A	N/A
2007/0032704	12/2006	Gandini et al.	N/A	N/A
2007/0055228	12/2006	Berg et al.	N/A	N/A
2007/0056596	12/2006	Fanney et al.	N/A	N/A
2007/0060935	12/2006	Schwardt et al.	N/A	N/A
2007/0063618	12/2006	Bromfield	N/A	N/A
2007/0066971	12/2006	Podhajsky	N/A	N/A
2007/0067123	12/2006	Jungerman	N/A	N/A
2007/0073185	12/2006	Nakao	N/A	N/A
2007/0073341	12/2006	Smith et al.	N/A	N/A
2007/0074584	12/2006	Talarico et al.	N/A	N/A
2007/0106317	12/2006	Shelton et al.	N/A	N/A
2007/0118115	12/2006	Artale et al.	N/A	N/A
2007/0129726	12/2006	Eder et al.	N/A	N/A
2007/0130771	12/2006	Ehlert et al.	N/A	N/A
2007/0135803	12/2006	Belson	N/A	N/A
2007/0149881	12/2006	Rabin	N/A	N/A
2007/0156163	12/2006	Davison et al.	N/A	N/A
2007/0166663	12/2006	Telles et al.	N/A	N/A
2007/0173803	12/2006	Wham et al.	N/A	N/A
2007/0173813	12/2006	Odom	N/A	N/A
2007/0173872	12/2006	Neuenfeldt	N/A	N/A
2007/0175955	12/2006	Shelton et al.	N/A	N/A
2007/0185474	12/2006	Nahen	N/A	N/A
2007/0191712	12/2006	Messerly et al.	N/A	N/A
2007/0191713	12/2006	Eichmann et al.	N/A	N/A
2007/0203483	12/2006	Kim et al.	N/A	N/A
2007/0208336	12/2006	Kim et al.	N/A	N/A
2007/0208340	12/2006	Ganz et al.	N/A	N/A
2007/0219481	12/2006	Babaev	N/A	N/A
2007/0232926	12/2006	Stulen et al.	N/A	N/A
2007/0232928	12/2006	Wiener et al.	N/A	N/A
2007/0236213	12/2006	Paden et al.	N/A	N/A
2007/0239101	12/2006	Kellogg	N/A	N/A
2007/0249941	12/2006	Salehi et al.	N/A	N/A
2007/0260242	12/2006	Dycus et al.	N/A	N/A
2007/0265560	12/2006	Soltani et al.	N/A	N/A
2007/0265613	12/2006	Edelstein et al.	N/A	N/A
2007/0265616	12/2006	Couture et al.	N/A	N/A
2007/0265620	12/2006	Kraas et al.	N/A	N/A
2007/0275348	12/2006	Lemon	N/A	N/A
2007/0287933	12/2006	Phan et al.	N/A	N/A
2007/0288055	12/2006	Lee	N/A	N/A
2007/0299895	12/2006	Johnson et al.	N/A	N/A
2008/0005213	12/2007	Holtzman	N/A	N/A
2008/0013809	12/2007	Zhu et al.	N/A	N/A
2008/0015473	12/2007	Shimizu	N/A	N/A

2008/0015575	12/2007	Odom et al.	N/A	N/A
2008/0033465	12/2007	Schmitz et al.	N/A	N/A
2008/0039746	12/2007	Hissong et al.	N/A	N/A
2008/0046122	12/2007	Manzo et al.	N/A	N/A
2008/0051812	12/2007	Schmitz et al.	N/A	N/A
2008/0058775	12/2007	Darian et al.	N/A	N/A
2008/0058845	12/2007	Shimizu et al.	N/A	N/A
2008/0071269	12/2007	Hilario et al.	N/A	N/A
2008/0077145	12/2007	Boyden et al.	N/A	N/A
2008/0082039	12/2007	Babaev	N/A	N/A
2008/0082098	12/2007	Tanaka et al.	N/A	N/A
2008/0097501	12/2007	Blier	N/A	N/A
2008/0114355	12/2007	Whayne et al.	N/A	N/A
2008/0114364	12/2007	Goldin et al.	N/A	N/A
2008/0122496	12/2007	Wagner	N/A	N/A
2008/0125768	12/2007	Tahara et al.	N/A	N/A
2008/0147058	12/2007	Horrell et al.	N/A	N/A
2008/0147062	12/2007	Truckai et al.	N/A	N/A
2008/0147092	12/2007	Rogge et al.	N/A	N/A
2008/0161809	12/2007	Schmitz et al.	N/A	N/A
2008/0167670	12/2007	Shelton et al.	N/A	N/A
2008/0171938	12/2007	Masuda et al.	N/A	N/A
2008/0177268	12/2007	Daum et al.	N/A	N/A
2008/0188755	12/2007	Hart	N/A	N/A
2008/0200940	12/2007	Eichmann et al.	N/A	N/A
2008/0208108	12/2007	Kimura	N/A	N/A
2008/0208231	12/2007	Ota et al.	N/A	N/A
2008/0214967	12/2007	Aranyi et al.	N/A	N/A
2008/0234709	12/2007	Houser	N/A	N/A
2008/0243162	12/2007	Shibata et al.	N/A	N/A
2008/0255413	12/2007	Zemlok et al.	N/A	N/A
2008/0275440	12/2007	Kratoska et al.	N/A	N/A
2008/0281200	12/2007	Voic et al.	N/A	N/A
2008/0281315	12/2007	Gines	N/A	N/A
2008/0287944	12/2007	Pearson et al.	N/A	N/A
2008/0287948	12/2007	Newton et al.	N/A	N/A
2008/0296346	12/2007	Shelton, IV et al.	N/A	N/A
2008/0300588	12/2007	Groth et al.	N/A	N/A
2009/0012516	12/2008	Curtis et al.	N/A	N/A
2009/0023985	12/2008	Ewers	N/A	N/A
2009/0036913	12/2008	Wiener et al.	N/A	N/A
2009/0043293	12/2008	Pankratov et al.	N/A	N/A
2009/0048537	12/2008	Lydon et al.	N/A	N/A
2009/0048589	12/2008	Takashino et al.	N/A	N/A
2009/0054886	12/2008	Yachi et al.	N/A	N/A
2009/0054889	12/2008	Newton et al.	N/A	N/A
2009/0054894	12/2008	Yachi	N/A	N/A
2009/0065565	12/2008	Cao	N/A	N/A
2009/0076506	12/2008	Baker	N/A	N/A
2009/0082716	12/2008	Akahoshi	N/A	N/A

2009/0082766	12/2008	Unger et al.	N/A	N/A
2009/0088745	12/2008	Hushka et al.	N/A	N/A
2009/0088785	12/2008	Masuda	N/A	N/A
2009/0090763	12/2008	Zemlok et al.	N/A	N/A
2009/0101692	12/2008	Whitman et al.	N/A	N/A
2009/0105750	12/2008	Price et al.	N/A	N/A
2009/0112206	12/2008	Dumbauld et al.	N/A	N/A
2009/0118751	12/2008	Wiener et al.	N/A	N/A
2009/0131885	12/2008	Akahoshi	N/A	N/A
2009/0131934	12/2008	Odom et al.	N/A	N/A
2009/0138025	12/2008	Stahler et al.	N/A	N/A
2009/0143678	12/2008	Keast et al.	N/A	N/A
2009/0143799	12/2008	Smith et al.	N/A	N/A
2009/0143800	12/2008	Deville et al.	N/A	N/A
2009/0157064	12/2008	Hodel	N/A	N/A
2009/0163807	12/2008	Sliwa	N/A	N/A
2009/0177119	12/2008	Heidner et al.	N/A	N/A
2009/0179923	12/2008	Amundson et al.	N/A	N/A
2009/0182322	12/2008	D'Amelio et al.	N/A	N/A
2009/0182331	12/2008	D'Amelio et al.	N/A	N/A
2009/0182332	12/2008	Long et al.	N/A	N/A
2009/0182333	12/2008	Eder et al.	N/A	N/A
2009/0192441	12/2008	Gelbart et al.	N/A	N/A
2009/0198272	12/2008	Kerver et al.	N/A	N/A
2009/0204114	12/2008	Odom	N/A	N/A
2009/0216157	12/2008	Yamada	N/A	N/A
2009/0223033	12/2008	Houser	N/A	N/A
2009/0240244	12/2008	Malis et al.	N/A	N/A
2009/0248021	12/2008	McKenna	606/51	A61B 18/1445
2009/0248022	12/2008	Falkenstein et al.	N/A	N/A
2009/0254077	12/2008	Craig	N/A	N/A
2009/0254080	12/2008	Honda	N/A	N/A
2009/0259149	12/2008	Tahara et al.	N/A	N/A
2009/0264909	12/2008	Beaupre	N/A	N/A
2009/0270771	12/2008	Takahashi	N/A	N/A
2009/0270812	12/2008	Litscher et al.	N/A	N/A
2009/0270853	12/2008	Yachi et al.	N/A	N/A
2009/0270891	12/2008	Beaupre	N/A	N/A
2009/0270899	12/2008	Carusillo et al.	N/A	N/A
2009/0287205	12/2008	Ingle	N/A	N/A
2009/0292283	12/2008	Odom	N/A	N/A
2009/0299141	12/2008	Downey et al.	N/A	N/A
2009/0306639	12/2008	Nevo et al.	N/A	N/A
2009/0327715	12/2008	Smith et al.	N/A	N/A
2010/0004508	12/2009	Naito et al.	N/A	N/A
2010/0022825	12/2009	Yoshie	N/A	N/A
2010/0030233	12/2009	Whitman et al.	N/A	N/A
2010/0034605	12/2009	Huckins et al.	N/A	N/A
2010/0036370	12/2009	Mirel et al.	N/A	N/A

2010/0036373	12/2009	Ward	N/A	N/A
2010/0042093	12/2009	Wham et al.	N/A	N/A
2010/0049180	12/2009	Wells et al.	N/A	N/A
2010/0057081	12/2009	Hanna	N/A	N/A
2010/0057118	12/2009	Dietz et al.	N/A	N/A
2010/0063437	12/2009	Nelson et al.	N/A	N/A
2010/0063525	12/2009	Beaupre et al.	N/A	N/A
2010/0063528	12/2009	Beaupre	N/A	N/A
2010/0081863	12/2009	Hess et al.	N/A	N/A
2010/0081864	12/2009	Hess et al.	N/A	N/A
2010/0081883	12/2009	Murray et al.	N/A	N/A
2010/0094323	12/2009	Isaacs et al.	N/A	N/A
2010/0106173	12/2009	Yoshimine	N/A	N/A
2010/0109480	12/2009	Forslund et al.	N/A	N/A
2010/0145335	12/2009	Johnson et al.	N/A	N/A
2010/0158307	12/2009	Kubota et al.	N/A	N/A
2010/0168741	12/2009	Sanai et al.	N/A	N/A
2010/0181966	12/2009	Sakakibara	N/A	N/A
2010/0187283	12/2009	Crainich et al.	N/A	N/A
2010/0193566	12/2009	Scheib et al.	N/A	N/A
2010/0204721	12/2009	Young et al.	N/A	N/A
2010/0222714	12/2009	Muir et al.	N/A	N/A
2010/0222752	12/2009	Collins, Jr. et al.	N/A	N/A
2010/0225209	12/2009	Goldberg et al.	N/A	N/A
2010/0228249	12/2009	Mohr et al.	N/A	N/A
2010/0228250	12/2009	Brogna	N/A	N/A
2010/0234906	12/2009	Koh	N/A	N/A
2010/0256635	12/2009	McKenna et al.	N/A	N/A
2010/0274160	12/2009	Yachi et al.	N/A	N/A
2010/0274244	12/2009	Heard	606/45	A61B 18/1442
2010/0274278	12/2009	Fleenor et al.	N/A	N/A
2010/0280368	12/2009	Can et al.	N/A	N/A
2010/0298743	12/2009	Nield et al.	N/A	N/A
2010/0305564	12/2009	Livneh	N/A	N/A
2010/0331742	12/2009	Masuda	N/A	N/A
2010/0331871	12/2009	Nield et al.	N/A	N/A
2011/0004233	12/2010	Muir et al.	N/A	N/A
2011/0015632	12/2010	Artale	N/A	N/A
2011/0015650	12/2010	Choi et al.	N/A	N/A
2011/0022032	12/2010	Zemlok et al.	N/A	N/A
2011/0028964	12/2010	Edwards	N/A	N/A
2011/0071523	12/2010	Dickhans	N/A	N/A
2011/0082494	12/2010	Kerr et al.	N/A	N/A
2011/0106141	12/2010	Nakamura	N/A	N/A
2011/0112400	12/2010	Emery et al.	N/A	N/A
2011/0125149	12/2010	El-Galley et al.	N/A	N/A
2011/0125151	12/2010	Strauss et al.	N/A	N/A
2011/0144640	12/2010	Heinrich et al.	N/A	N/A

2011/0155781	12/2010	Swensgard	227/176.1	A61B 17/068
2011/0160725	12/2010	Kabaya et al.	N/A	N/A
2011/0238010	12/2010	Kirschenman et al.	N/A	N/A
2011/0238079	12/2010	Hannaford et al.	N/A	N/A
2011/0273465	12/2010	Konishi et al.	N/A	N/A
2011/0278343	12/2010	Knodel et al.	N/A	N/A
2011/0279268	12/2010	Konishi et al.	N/A	N/A
2011/0284014	12/2010	Cadeddu et al.	N/A	N/A
2011/0290856	12/2010	Shelton, IV et al.	N/A	N/A
2011/0295295	12/2010	Shelton, IV et al.	N/A	N/A
2011/0306967	12/2010	Payne et al.	N/A	N/A
2011/0313415	12/2010	Fernandez et al.	N/A	N/A
2012/0004655	12/2011	Kim et al.	N/A	N/A
2012/0016413	12/2011	Timm et al.	N/A	N/A
2012/0022519	12/2011	Huang et al.	N/A	N/A
2012/0022526	12/2011	Aldridge et al.	N/A	N/A
2012/0022528	12/2011	White et al.	N/A	N/A
2012/0022583	12/2011	Sugalski et al.	N/A	N/A
2012/0041358	12/2011	Mann et al.	N/A	N/A
2012/0053597	12/2011	Anvari et al.	N/A	N/A
2012/0059286	12/2011	Hastings et al.	N/A	N/A
2012/0059289	12/2011	Nield et al.	N/A	N/A
2012/0071863	12/2011	Lee et al.	N/A	N/A
2012/0078244	12/2011	Worrell et al.	N/A	N/A
2012/0080344	12/2011	Shelton, IV	N/A	N/A
2012/0101493	12/2011	Masuda et al.	N/A	N/A
2012/0101495	12/2011	Young et al.	N/A	N/A
2012/0109186	12/2011	Parrott et al.	N/A	N/A
2012/0116222	12/2011	Sawada et al.	N/A	N/A
2012/0116265	12/2011	Houser et al.	N/A	N/A
2012/0116266	12/2011	Houser et al.	N/A	N/A
2012/0116381	12/2011	Houser et al.	N/A	N/A
2012/0136279	12/2011	Tanaka et al.	N/A	N/A
2012/0136347	12/2011	Brustad et al.	N/A	N/A
2012/0136386	12/2011	Kishida et al.	N/A	N/A
2012/0143182	12/2011	Ullrich et al.	N/A	N/A
2012/0143211	12/2011	Kishi	N/A	N/A
2012/0150049	12/2011	Zielinski et al.	N/A	N/A
2012/0150169	12/2011	Zielinski et al.	N/A	N/A
2012/0172904	12/2011	Muir et al.	N/A	N/A
2012/0191091	12/2011	Allen	N/A	N/A
2012/0193396	12/2011	Zemlok et al.	N/A	N/A
2012/0211542	12/2011	Racenet	N/A	N/A
2012/0226266	12/2011	Ghosal et al.	N/A	N/A
2012/0234893	12/2011	Schuckmann et al.	N/A	N/A
2012/0253328	12/2011	Cunningham et al.	N/A	N/A
2012/0253329	12/2011	Zemlok et al.	N/A	N/A
2012/0265241	12/2011	Hart et al.	N/A	N/A
2012/0296239	12/2011	Chernov et al.	N/A	N/A

2012/0296325	12/2011	Takashino	N/A	N/A
2012/0296371	12/2011	Kappus et al.	N/A	N/A
2013/0023925	12/2012	Mueller	N/A	N/A
2013/0071282	12/2012	Fry	N/A	N/A
2013/0085510	12/2012	Stefanchik et al.	N/A	N/A
2013/0103031	12/2012	Garrison	N/A	N/A
2013/0123776	12/2012	Monson et al.	N/A	N/A
2013/0158659	12/2012	Bergs et al.	N/A	N/A
2013/0158660	12/2012	Bergs et al.	N/A	N/A
2013/0165929	12/2012	Muir et al.	N/A	N/A
2013/0190760	12/2012	Allen, IV et al.	N/A	N/A
2013/0214025	12/2012	Zemlok et al.	N/A	N/A
2013/0253256	12/2012	Griffith et al.	N/A	N/A
2013/0253480	12/2012	Kimball et al.	N/A	N/A
2013/0264369	12/2012	Whitman	N/A	N/A
2013/0267874	12/2012	Marcotte et al.	N/A	N/A
2013/0277410	12/2012	Fernandez et al.	N/A	N/A
2013/0296843	12/2012	Boudreaux et al.	N/A	N/A
2013/0321425	12/2012	Greene et al.	N/A	N/A
2013/0334989	12/2012	Kataoka	N/A	N/A
2013/0345701	12/2012	Allen, IV et al.	N/A	N/A
2014/0001231	12/2013	Shelton, IV et al.	N/A	N/A
2014/0001234	12/2013	Shelton, IV et al.	N/A	N/A
2014/0005640	12/2013	Shelton, IV et al.	N/A	N/A
2014/0005663	12/2013	Heard et al.	N/A	N/A
2014/0005678	12/2013	Shelton, IV et al.	N/A	N/A
2014/0005702	12/2013	Timm et al.	N/A	N/A
2014/0005705	12/2013	Weir et al.	N/A	N/A
2014/0005718	12/2013	Shelton, IV et al.	N/A	N/A
2014/0014544	12/2013	Bugnard et al.	N/A	N/A
2014/0077426	12/2013	Park	N/A	N/A
2014/0107538	12/2013	Wiener et al.	N/A	N/A
2014/0121569	12/2013	Schafer et al.	N/A	N/A
2014/0135804	12/2013	Weisenburgh, II et al.	N/A	N/A
2014/0163541	12/2013	Shelton, IV et al.	N/A	N/A
2014/0163549	12/2013	Yates et al.	N/A	N/A
2014/0180274	12/2013	Kabaya et al.	N/A	N/A
2014/0180310	12/2013	Blumenkranz et al.	N/A	N/A
2014/0194868	12/2013	Sanai et al.	N/A	N/A
2014/0194874	12/2013	Dietz et al.	N/A	N/A
2014/0194875	12/2013	Reschke et al.	N/A	N/A
2014/0207124	12/2013	Aldridge et al.	N/A	N/A
2014/0207135	12/2013	Winter	N/A	N/A
2014/0221994	12/2013	Reschke	N/A	N/A
2014/0236152	12/2013	Walberg et al.	N/A	N/A
2014/0246475	12/2013	Hall et al.	N/A	N/A
2014/0249557	12/2013	Koch et al.	N/A	N/A
2014/0263541	12/2013	Leimbach et al.	N/A	N/A
2014/0263552	12/2013	Hall et al.	N/A	N/A

2014/0276768	12/2013	Juergens et al.	N/A	N/A
2014/0276794	12/2013	Batchelor et al.	N/A	N/A
2014/0276797	12/2013	Batchelor et al.	N/A	N/A
2014/0276798	12/2013	Batchelor et al.	N/A	N/A
2014/0303605	12/2013	Boyden et al.	N/A	N/A
2014/0303612	12/2013	Williams	N/A	N/A
2014/0357984	12/2013	Wallace et al.	N/A	N/A
2014/0373003	12/2013	Greze et al.	N/A	N/A
2015/0014392	12/2014	Williams et al.	N/A	N/A
2015/0025528	12/2014	Arts	N/A	N/A
2015/0032150	12/2014	Ishida et al.	N/A	N/A
2015/0048140	12/2014	Penna et al.	N/A	N/A
2015/0066027	12/2014	Garrison et al.	N/A	N/A
2015/0080876	12/2014	Worrell et al.	N/A	N/A
2015/0080887	12/2014	Sobajima et al.	N/A	N/A
2015/0080889	12/2014	Cunningham et al.	N/A	N/A
2015/0088122	12/2014	Jensen	N/A	N/A
2015/0100056	12/2014	Nakamura	N/A	N/A
2015/0112335	12/2014	Boudreaux et al.	N/A	N/A
2015/0119901	12/2014	Steege	N/A	N/A
2015/0157356	12/2014	Gee	N/A	N/A
2015/0164533	12/2014	Felder et al.	N/A	N/A
2015/0164534	12/2014	Felder et al.	N/A	N/A
2015/0164535	12/2014	Felder et al.	N/A	N/A
2015/0164536	12/2014	Czarnecki et al.	N/A	N/A
2015/0164537	12/2014	Cagle et al.	N/A	N/A
2015/0164538	12/2014	Aldridge et al.	N/A	N/A
2015/0230796	12/2014	Calderoni	N/A	N/A
2015/0238260	12/2014	Nau, Jr.	N/A	N/A
2015/0272557	12/2014	Overmyer et al.	N/A	N/A
2015/0272571	12/2014	Leimbach et al.	N/A	N/A
2015/0272580	12/2014	Leimbach et al.	N/A	N/A
2015/0272582	12/2014	Leimbach et al.	N/A	N/A
2015/0272657	12/2014	Yates et al.	N/A	N/A
2015/0272659	12/2014	Boudreaux et al.	N/A	N/A
2015/0282879	12/2014	Ruelas	N/A	N/A
2015/0289364	12/2014	Ilkko et al.	N/A	N/A
2015/0313667	12/2014	Allen, IV	N/A	N/A
2015/0317899	12/2014	Dumbauld et al.	N/A	N/A
2015/0351765	12/2014	Valentine et al.	N/A	N/A
2015/0351857	12/2014	Vander Poorten et al.	N/A	N/A
2015/0374430	12/2014	Weiler et al.	N/A	N/A
2015/0374457	12/2014	Colby	N/A	N/A
2016/0000437	12/2015	Giordano et al.	N/A	N/A
2016/0038228	12/2015	Daniel et al.	N/A	N/A
2016/0044841	12/2015	Chamberlain	N/A	N/A
2016/0045248	12/2015	Unger et al.	N/A	N/A
2016/0051314	12/2015	Batchelor et al.	N/A	N/A
2016/0051316	12/2015	Boudreaux	N/A	N/A

2016/0066913	12/2015	Swayze et al.	N/A	N/A
2016/0120601	12/2015	Boudreaux et al.	N/A	N/A
2016/0175025	12/2015	Strobl	N/A	N/A
2016/0175029	12/2015	Witt et al.	N/A	N/A
2016/0206342	12/2015	Robertson et al.	N/A	N/A
2016/0228171	12/2015	Boudreaux	N/A	N/A
2016/0249910	12/2015	Shelton, IV et al.	N/A	N/A
2016/0262786	12/2015	Madan et al.	N/A	N/A
2016/0270842	12/2015	Strobl et al.	N/A	N/A
2016/0296251	12/2015	Olson et al.	N/A	N/A
2016/0296252	12/2015	Olson et al.	N/A	N/A
2016/0296270	12/2015	Strobl et al.	N/A	N/A
2016/0317216	12/2015	Hermes et al.	N/A	N/A
2016/0331455	12/2015	Hancock et al.	N/A	N/A
2016/0358849	12/2015	Jur et al.	N/A	N/A
2017/0020614	12/2016	Jackson et al.	N/A	N/A
2017/0065331	12/2016	Mayer et al.	N/A	N/A
2017/0086909	12/2016	Yates et al.	N/A	N/A
2017/0119426	12/2016	Akagane	N/A	N/A
2017/0135751	12/2016	Rothweiler et al.	N/A	N/A
2017/0164972	12/2016	Johnson et al.	N/A	N/A
2017/0164997	12/2016	Johnson et al.	N/A	N/A
2017/0189095	12/2016	Danziger et al.	N/A	N/A
2017/0202595	12/2016	Shelton, IV	N/A	N/A
2017/0209145	12/2016	Swayze et al.	N/A	N/A
2017/0224332	12/2016	Hunter et al.	N/A	N/A
2017/0224405	12/2016	Takashino et al.	N/A	N/A
2017/0231628	12/2016	Shelton, IV et al.	N/A	N/A
2017/0281186	12/2016	Shelton, IV et al.	N/A	N/A
2017/0296169	12/2016	Yates et al.	N/A	N/A
2017/0296177	12/2016	Harris et al.	N/A	N/A
2017/0296180	12/2016	Harris et al.	N/A	N/A
2017/0303954	12/2016	Ishii	N/A	N/A
2017/0312018	12/2016	Trees et al.	N/A	N/A
2017/0325874	12/2016	Noack et al.	N/A	N/A
2017/0333073	12/2016	Faller et al.	N/A	N/A
2017/0348043	12/2016	Wang et al.	N/A	N/A
2017/0348044	12/2016	Wang et al.	N/A	N/A
2017/0367772	12/2016	Gunn et al.	N/A	N/A
2018/0014872	12/2017	Dickerson	N/A	N/A
2018/0085157	12/2017	Batchelor et al.	N/A	N/A
2018/0132850	12/2017	Leimbach et al.	N/A	N/A
2018/0168575	12/2017	Simms et al.	N/A	N/A
2018/0168577	12/2017	Aronhalt et al.	N/A	N/A
2018/0168579	12/2017	Aronhalt et al.	N/A	N/A
2018/0168592	12/2017	Overmyer et al.	N/A	N/A
2018/0168598	12/2017	Shelton, IV et al.	N/A	N/A
2018/0168608	12/2017	Shelton, IV et al.	N/A	N/A
2018/0168609	12/2017	Fanelli et al.	N/A	N/A
2018/0168610	12/2017	Shelton, IV et al.	N/A	N/A

2018/0168615	12/2017	Shelton, IV et al.	N/A	N/A
2018/0168618	12/2017	Scott et al.	N/A	N/A
2018/0168619	12/2017	Scott et al.	N/A	N/A
2018/0168623	12/2017	Simms et al.	N/A	N/A
2018/0168625	12/2017	Posada et al.	N/A	N/A
2018/0168633	12/2017	Shelton, IV et al.	N/A	N/A
2018/0168647	12/2017	Shelton, IV et al.	N/A	N/A
2018/0168648	12/2017	Shelton, IV et al.	N/A	N/A
2018/0168650	12/2017	Shelton, IV et al.	N/A	N/A
2018/0188125	12/2017	Park et al.	N/A	N/A
2018/0206904	12/2017	Felder et al.	N/A	N/A
2018/0221045	12/2017	Zimmerman et al.	N/A	N/A
2018/0235691	12/2017	Voegele et al.	N/A	N/A
2018/0250066	12/2017	Ding et al.	N/A	N/A
2018/0271578	12/2017	Coulombe	N/A	N/A
2018/0289432	12/2017	Kostrzewski et al.	N/A	N/A
2018/0303493	12/2017	Chapolini	N/A	N/A
2018/0325517	12/2017	Wingardner et al.	N/A	N/A
2018/0333179	12/2017	Weisenburgh, II et al.	N/A	N/A
2018/0353245	12/2017	Mccloud et al.	N/A	N/A
2018/0368843	12/2017	Shelton, IV et al.	N/A	N/A
2018/0368844	12/2017	Bakos et al.	N/A	N/A
2019/0000459	12/2018	Shelton, IV et al.	N/A	N/A
2019/0000461	12/2018	Shelton, IV et al.	N/A	N/A
2019/0000462	12/2018	Shelton, IV et al.	N/A	N/A
2019/0000474	12/2018	Shelton, IV et al.	N/A	N/A
2019/0000475	12/2018	Shelton, IV et al.	N/A	N/A
2019/0000476	12/2018	Shelton, IV et al.	N/A	N/A
2019/0000477	12/2018	Shelton, IV et al.	N/A	N/A
2019/0029746	12/2018	Dudhedia et al.	N/A	N/A
2019/0038279	12/2018	Shelton, IV et al.	N/A	N/A
2019/0038282	12/2018	Shelton, IV et al.	N/A	N/A
2019/0038283	12/2018	Shelton, IV et al.	N/A	N/A
2019/0053818	12/2018	Nelson et al.	N/A	N/A
2019/0104919	12/2018	Shelton, IV et al.	N/A	N/A
2019/0105067	12/2018	Boudreaux et al.	N/A	N/A
2019/0117293	12/2018	Kano et al.	N/A	N/A
2019/0125361	12/2018	Shelton, IV et al.	N/A	N/A
2019/0125384	12/2018	Scheib et al.	N/A	N/A
2019/0125390	12/2018	Shelton, IV et al.	N/A	N/A
2019/0175258	12/2018	Tsuruta	N/A	N/A
2019/0183504	12/2018	Shelton, IV et al.	N/A	N/A
2019/0200844	12/2018	Shelton, IV et al.	N/A	N/A
2019/0200977	12/2018	Shelton, IV et al.	N/A	N/A
2019/0200981	12/2018	Harris et al.	N/A	N/A
2019/0200987	12/2018	Shelton, IV et al.	N/A	N/A
2019/0201020	12/2018	Shelton, IV et al.	N/A	N/A
2019/0201023	12/2018	Shelton, IV et al.	N/A	N/A
2019/0201029	12/2018	Shelton, IV et al.	N/A	N/A

2019/0201030	12/2018	Shelton, IV et al.	N/A	N/A
2019/0201045	12/2018	Yates et al.	N/A	N/A
2019/0201046	12/2018	Shelton, IV et al.	N/A	N/A
2019/0201047	12/2018	Yates et al.	N/A	N/A
2019/0201048	12/2018	Stulen et al.	N/A	N/A
2019/0201104	12/2018	Shelton, IV et al.	N/A	N/A
2019/0201136	12/2018	Shelton, IV et al.	N/A	N/A
2019/0201137	12/2018	Shelton, IV et al.	N/A	N/A
2019/0201594	12/2018	Shelton, IV et al.	N/A	N/A
2019/0206562	12/2018	Shelton, IV et al.	N/A	N/A
2019/0206563	12/2018	Shelton, IV et al.	N/A	N/A
2019/0206564	12/2018	Shelton, IV et al.	N/A	N/A
2019/0206565	12/2018	Shelton, IV	N/A	N/A
2019/0206569	12/2018	Shelton, IV et al.	N/A	N/A
2019/0208641	12/2018	Yates et al.	N/A	N/A
2019/0209201	12/2018	Boudreaux et al.	N/A	N/A
2019/0223941	12/2018	Kitamura et al.	N/A	N/A
2019/0262030	12/2018	Faller et al.	N/A	N/A
2019/0269455	12/2018	Mensch et al.	N/A	N/A
2019/0274700	12/2018	Robertson et al.	N/A	N/A
2019/0282288	12/2018	Boudreaux	N/A	N/A
2019/0290265	12/2018	Shelton, IV et al.	N/A	N/A
2019/0298340	12/2018	Shelton, IV et al.	N/A	N/A
2019/0298350	12/2018	Shelton, IV et al.	N/A	N/A
2019/0298352	12/2018	Shelton, IV et al.	N/A	N/A
2019/0298353	12/2018	Shelton, IV et al.	N/A	N/A
2019/0366562	12/2018	Zhang et al.	N/A	N/A
2019/0388091	12/2018	Eschbach et al.	N/A	N/A
2020/0030021	12/2019	Yates et al.	N/A	N/A
2020/0054321	12/2019	Harris et al.	N/A	N/A
2020/0054382	12/2019	Yates et al.	N/A	N/A
2020/0078076	12/2019	Henderson et al.	N/A	N/A
2020/0078085	12/2019	Yates et al.	N/A	N/A
2020/0078106	12/2019	Henderson et al.	N/A	N/A
2020/0078609	12/2019	Messerly et al.	N/A	N/A
2020/0085465	12/2019	Timm et al.	N/A	N/A
2020/0100825	12/2019	Henderson et al.	N/A	N/A
2020/0100830	12/2019	Henderson et al.	N/A	N/A
2020/0113622	12/2019	Honegger	N/A	N/A
2020/0129261	12/2019	Eschbach	N/A	N/A
2020/0138473	12/2019	Shelton, IV et al.	N/A	N/A
2020/0188047	12/2019	Itkowitz et al.	N/A	N/A
2020/0222111	12/2019	Yates et al.	N/A	N/A
2020/0222112	12/2019	Hancock et al.	N/A	N/A
2020/0229833	12/2019	Vakharia et al.	N/A	N/A
2020/0229834	12/2019	Olson et al.	N/A	N/A
2020/0237434	12/2019	Scheib et al.	N/A	N/A
2020/0261075	12/2019	Boudreaux et al.	N/A	N/A
2020/0261078	12/2019	Bakos et al.	N/A	N/A
2020/0261081	12/2019	Boudreaux et al.	N/A	N/A

2020/0261083	12/2019	Bakos et al.	N/A	N/A
2020/0261085	12/2019	Boudreaux et al.	N/A	N/A
2020/0261086	12/2019	Zeiner et al.	N/A	N/A
2020/0261087	12/2019	Timm et al.	N/A	N/A
2020/0261088	12/2019	Harris et al.	N/A	N/A
2020/0261141	12/2019	Wiener et al.	N/A	N/A
2020/0268430	12/2019	Takei et al.	N/A	N/A
2020/0268433	12/2019	Wiener et al.	N/A	N/A
2020/0305870	12/2019	Shelton, IV	N/A	N/A
2020/0315623	12/2019	Eisinger et al.	N/A	N/A
2020/0315712	12/2019	Jasperson et al.	N/A	N/A
2020/0338370	12/2019	Wiener et al.	N/A	N/A
2020/0405296	12/2019	Shelton, IV et al.	N/A	N/A
2020/0405302	12/2019	Shelton, IV et al.	N/A	N/A
2020/0405312	12/2019	Shelton, IV et al.	N/A	N/A
2020/0405314	12/2019	Shelton, IV et al.	N/A	N/A
2020/0405316	12/2019	Shelton, IV et al.	N/A	N/A
2020/0405409	12/2019	Shelton, IV et al.	N/A	N/A
2020/0405410	12/2019	Shelton, IV	N/A	N/A
2020/0405436	12/2019	Shelton, IV et al.	N/A	N/A
2020/0405437	12/2019	Shelton, IV et al.	N/A	N/A
2020/0405438	12/2019	Shelton, IV et al.	N/A	N/A
2020/0405439	12/2019	Shelton, IV et al.	N/A	N/A
2020/0410177	12/2019	Shelton, IV	N/A	N/A
2020/0410180	12/2019	Shelton, IV et al.	N/A	N/A
2021/0052313	12/2020	Shelton, IV et al.	N/A	N/A
2021/0100578	12/2020	Weir et al.	N/A	N/A
2021/0153927	12/2020	Ross et al.	N/A	N/A
2021/0177481	12/2020	Shelton, IV et al.	N/A	N/A
2021/0177494	12/2020	Houser et al.	N/A	N/A
2021/0177496	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186492	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186493	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186494	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186495	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186497	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186498	12/2020	Boudreaux et al.	N/A	N/A
2021/0186499	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186500	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186501	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186502	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186503	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186504	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186505	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186507	12/2020	Shelton, IV et al.	N/A	N/A
2021/0186553	12/2020	Green et al.	N/A	N/A
2021/0186554	12/2020	Green et al.	N/A	N/A
2021/0196263	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196265	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196266	12/2020	Shelton, IV et al.	N/A	N/A

2021/0196267	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196268	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196269	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196270	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196271	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196301	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196302	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196305	12/2020	Strobl	N/A	N/A
2021/0196306	12/2020	Estera et al.	N/A	N/A
2021/0196307	12/2020	Shelton, IV	N/A	N/A
2021/0196334	12/2020	Sarley et al.	N/A	N/A
2021/0196335	12/2020	Messerly et al.	N/A	N/A
2021/0196336	12/2020	Faller et al.	N/A	N/A
2021/0196343	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196344	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196345	12/2020	Messerly et al.	N/A	N/A
2021/0196346	12/2020	Leuck et al.	N/A	N/A
2021/0196349	12/2020	Fiebig et al.	N/A	N/A
2021/0196350	12/2020	Fiebig et al.	N/A	N/A
2021/0196351	12/2020	Sarley et al.	N/A	N/A
2021/0196352	12/2020	Messerly et al.	N/A	N/A
2021/0196353	12/2020	Gee et al.	N/A	N/A
2021/0196354	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196355	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196356	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196357	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196358	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196359	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196360	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196361	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196362	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196363	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196364	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196365	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196366	12/2020	Shelton, IV et al.	N/A	N/A
2021/0196367	12/2020	Salguero et al.	N/A	N/A
2021/0212744	12/2020	Shelton, IV et al.	N/A	N/A
2021/0212754	12/2020	Olson	N/A	N/A
2021/0220036	12/2020	Shelton, IV et al.	N/A	N/A
2021/0236195	12/2020	Asher et al.	N/A	N/A
2021/0282804	12/2020	Worrell et al.	N/A	N/A
2021/0393288	12/2020	Shelton, IV et al.	N/A	N/A
2021/0393314	12/2020	Wiener et al.	N/A	N/A
2021/0393319	12/2020	Shelton, IV et al.	N/A	N/A
2022/0039891	12/2021	Stulen et al.	N/A	N/A
2022/0071655	12/2021	Price et al.	N/A	N/A
2022/0167982	12/2021	Shelton, IV et al.	N/A	N/A
2022/0168005	12/2021	Aldridge et al.	N/A	N/A
2022/0168039	12/2021	Worrell et al.	N/A	N/A
2022/0226014	12/2021	Clauda, IV et al.	N/A	N/A

2022/0304736	12/2021	Boudreaux	N/A	N/A
2022/0313297	12/2021	Aldridge et al.	N/A	N/A
2022/0346863	12/2021	Yates et al.	N/A	N/A
2022/0387067	12/2021	Faller et al.	N/A	N/A
2022/0406452	12/2021	Shelton, IV	N/A	N/A
2023/0038162	12/2022	Timm et al.	N/A	N/A
2023/0048996	12/2022	Vakharia et al.	N/A	N/A
2023/0270486	12/2022	Wiener et al.	N/A	N/A
2023/0277205	12/2022	Olson et al.	N/A	N/A
2023/0372743	12/2022	Wiener et al.	N/A	N/A
2023/0380880	12/2022	Wiener et al.	N/A	N/A
2023/0397909	12/2022	Shelton, IV et al.	N/A	N/A

FOREIGN PATENT DOCUMENTS

Patent No.	Application Date	Country	CPC
2535467	12/1992	CA	N/A
2460047	12/2000	CN	N/A
1634601	12/2004	CN	N/A
1775323	12/2005	CN	N/A
1922563	12/2006	CN	N/A
2868227	12/2006	CN	N/A
201029899	12/2007	CN	N/A
101474081	12/2008	CN	N/A
101516285	12/2008	CN	N/A
101522112	12/2008	CN	N/A
102100582	12/2010	CN	N/A
102149312	12/2010	CN	N/A
202027624	12/2010	CN	N/A
102792181	12/2011	CN	N/A
103281982	12/2012	CN	N/A
103379853	12/2012	CN	N/A
203468630	12/2013	CN	N/A
104001276	12/2013	CN	N/A
104013444	12/2013	CN	N/A
104434298	12/2014	CN	N/A
107374752	12/2016	CN	N/A
3904558	12/1989	DE	N/A
9210327	12/1991	DE	N/A
4300307	12/1993	DE	N/A
29623113	12/1996	DE	N/A
20004812	12/1999	DE	N/A
20021619	12/2000	DE	N/A
10042606	12/2000	DE	N/A
10201569	12/2002	DE	N/A
102012109037	12/2013	DE	N/A
0171967	12/1985	EP	N/A
0336742	12/1988	EP	N/A
0136855	12/1988	EP	N/A
0468194	12/1991	EP	N/A

0705571	12/1995	EP	N/A
1698289	12/2005	EP	N/A
1862133	12/2006	EP	N/A
1972264	12/2007	EP	N/A
2060238	12/2008	EP	N/A
1747761	12/2008	EP	N/A
2131760	12/2008	EP	N/A
1214913	12/2009	EP	N/A
1946708	12/2010	EP	N/A
1767164	12/2012	EP	N/A
2578172	12/2012	EP	N/A
2668922	12/2012	EP	N/A
2076195	12/2014	EP	N/A
2510891	12/2015	EP	N/A
3476302	12/2018	EP	N/A
3476331	12/2018	EP	N/A
3694298	12/2019	EP	N/A
2032221	12/1979	GB	N/A
2317566	12/1997	GB	N/A
S50100891	12/1974	JP	N/A
S5968513	12/1983	JP	N/A
S59141938	12/1983	JP	N/A
S62221343	12/1986	JP	N/A
S62227343	12/1986	JP	N/A
S62292153	12/1986	JP	N/A
S62292154	12/1986	JP	N/A
S63109386	12/1987	JP	N/A
S63315049	12/1987	JP	N/A
H01151452	12/1988	JP	N/A
H01198540	12/1988	JP	N/A
H0271510	12/1989	JP	N/A
H02286149	12/1989	JP	N/A
H02292193	12/1989	JP	N/A
H0337061	12/1990	JP	N/A
H0425707	12/1991	JP	N/A
H0464351	12/1991	JP	N/A
H0430508	12/1991	JP	N/A
H04152942	12/1991	JP	N/A
H 0541716	12/1992	JP	N/A
H0576482	12/1992	JP	N/A
H0595955	12/1992	JP	N/A
H05115490	12/1992	JP	N/A
H0670938	12/1993	JP	N/A
H06104503	12/1993	JP	N/A
H0824266	12/1995	JP	N/A
H08229050	12/1995	JP	N/A
H08275951	12/1995	JP	N/A
H08299351	12/1995	JP	N/A
H08336545	12/1995	JP	N/A
H09130655	12/1996	JP	N/A

H09135553	12/1996	JP	N/A
H09140722	12/1996	JP	N/A
H105237	12/1997	JP	N/A
10127654	12/1997	JP	N/A
H10295700	12/1997	JP	N/A
H11128238	12/1998	JP	N/A
H11169381	12/1998	JP	N/A
2000210299	12/1999	JP	N/A
2000271142	12/1999	JP	N/A
2000271145	12/1999	JP	N/A
2000287987	12/1999	JP	N/A
2001029353	12/2000	JP	N/A
2002059380	12/2001	JP	N/A
2002186901	12/2001	JP	N/A
2002263579	12/2001	JP	N/A
2002330977	12/2001	JP	N/A
2003000612	12/2002	JP	N/A
2003010201	12/2002	JP	N/A
2003116870	12/2002	JP	N/A
2003126104	12/2002	JP	N/A
2003126110	12/2002	JP	N/A
2003153919	12/2002	JP	N/A
2003339730	12/2002	JP	N/A
2004129871	12/2003	JP	N/A
2004147701	12/2003	JP	N/A
2005003496	12/2004	JP	N/A
2005027026	12/2004	JP	N/A
2005074088	12/2004	JP	N/A
2005337119	12/2004	JP	N/A
2006068396	12/2005	JP	N/A
2006081664	12/2005	JP	N/A
2006114072	12/2005	JP	N/A
2006217716	12/2005	JP	N/A
2006288431	12/2005	JP	N/A
2007037568	12/2006	JP	N/A
200801876	12/2007	JP	N/A
2008017876	12/2007	JP	N/A
200833644	12/2007	JP	N/A
2008188160	12/2007	JP	N/A
D1339835	12/2007	JP	N/A
2010009686	12/2009	JP	N/A
2010121865	12/2009	JP	N/A
2012071186	12/2011	JP	N/A
2012223582	12/2011	JP	N/A
2012235658	12/2011	JP	N/A
2013126430	12/2012	JP	N/A
100789356	12/2006	KR	N/A
101298237	12/2012	KR	N/A
2154437	12/1999	RU	N/A
22035	12/2001	RU	N/A

2201169	12/2002	RU	N/A
2405603	12/2009	RU	N/A
2013119977	12/2013	RU	N/A
850068	12/1980	SU	N/A
WO-8103272	12/1980	WO	N/A
WO-9308757	12/1992	WO	N/A
WO-9314708	12/1992	WO	N/A
WO-9421183	12/1993	WO	N/A
WO-9424949	12/1993	WO	N/A
WO-9639086	12/1995	WO	N/A
WO-9712557	12/1996	WO	N/A
WO-9800069	12/1997	WO	N/A
WO-9840015	12/1997	WO	N/A
WO-9920213	12/1998	WO	N/A
WO-9923960	12/1998	WO	N/A
WO-0024330	12/1999	WO	N/A
WO-0064358	12/1999	WO	N/A
WO-0128444	12/2000	WO	N/A
WO-0167970	12/2000	WO	N/A
WO-0172251	12/2000	WO	N/A
WO-0195810	12/2000	WO	N/A
WO-02080793	12/2001	WO	N/A
WO-03095028	12/2002	WO	N/A
WO-2004037095	12/2003	WO	N/A
WO-2004078051	12/2003	WO	N/A
WO-2004098426	12/2003	WO	N/A
WO-2006091494	12/2005	WO	N/A
WO-2007008710	12/2006	WO	N/A
WO-2008118709	12/2007	WO	N/A
WO-2008130793	12/2007	WO	N/A
WO-2010027109	12/2009	WO	N/A
WO-2010104755	12/2009	WO	N/A
WO-2011008672	12/2010	WO	N/A
WO-2011044343	12/2010	WO	N/A
WO-2011052939	12/2010	WO	N/A
WO-2011060031	12/2010	WO	N/A
WO-2011092464	12/2010	WO	N/A
WO-2012044606	12/2011	WO	N/A
WO-2012061722	12/2011	WO	N/A
WO-2012088535	12/2011	WO	N/A
WO-2012150567	12/2011	WO	N/A
WO-2016130844	12/2015	WO	N/A
WO-2019130090	12/2018	WO	N/A
WO-2019130113	12/2018	WO	N/A

OTHER PUBLICATIONS

Weir, C.E., “Rate of shrinkage of tendon collagen—heat, entropy and free energy of activation of the shrinkage of untreated tendon. Effect of acid salt, pickle, and tannage on the activation of tendon collagen.” Journal of the American Leather Chemists Association, 44, pp. 108-140 (1949). cited by applicant

Henriques. F.C., "Studies in thermal injury V. The predictability and the significance of thermally induced rate processes leading to irreversible epidermal injury." Archives of Pathology, 434, pp. 489-502 (1947). cited by applicant

Arnoczky et al., "Thermal Modification of Connective Tissues: Basic Science Considerations and Clinical Implications," J. Am Acad Orthop Surg, vol. 8, No. 5, pp. 305-313 (Sep./Oct. 2000). cited by applicant

Chen et al., "Heat-Induced Changes in the Mechanics of a Collagenous Tissue: Isothermal Free Shrinkage," Transactions of the ASME, vol. 119, pp. 372-378 (Nov. 1997). cited by applicant

Chen et al., "Heat-Induced Changes in the Mechanics of a Collagenous Tissue: Isothermal, Isotonic Shrinkage," Transactions of the ASME, vol. 120, pp. 382-388 (Jun. 1998). cited by applicant

Chen et al., "Phenomenological Evolution Equations for Heat-Induced Shrinkage of a Collagenous Tissue," IEEE Transactions on Biomedical Engineering, vol. 45, No. 10, pp. 1234-1240 (Oct. 1998). cited by applicant

Harris et al., "Kinetics of Thermal Damage to a Collagenous Membrane Under Biaxial Isotonic Loading," IEEE Transactions on Biomedical Engineering, vol. 51, No. 2, pp. 371-379 (Feb. 2004). cited by applicant

Harris et al., "Altered Mechanical Behavior of Epicardium Due to Isothermal Heating Under Biaxial Isotonic Loads," Journal of Biomechanical Engineering, vol. 125, pp. 381-388 (Jun. 2003). cited by applicant

Lee et al., "A multi-sample denaturation temperature tester for collagenous biomaterials," Med. Eng. Phys., vol. 17, No. 2, pp. 115-121 (Mar. 1995). cited by applicant

Moran et al., "Thermally Induced Shrinkage of Joint Capsule," Clinical Orthopaedics and Related Research, No. 281, pp. 248-255 (Dec. 2000). cited by applicant

Wall et al., "Thermal modification of collagen," J Shoulder Elbow Surg, No. 8, pp. 339-344 (Jul./Aug. 1999). cited by applicant

Wells et al., "Altered Mechanical Behavior of Epicardium Under Isothermal Biaxial Loading," Transactions of the ASME, Journal of Biomedical Engineering, vol. 126, pp. 492-497 (Aug. 2004). cited by applicant

Gibson, "Magnetic Refrigerator Successfully Tested," U.S. Department of Energy Research News, accessed online on Aug. 6, 2010 at <http://www.eurekalert.org/features/doe/2001-11/dl-mrs062802.php> (Nov. 1, 2001). cited by applicant

Humphrey, J.D., "Continuum Thermomechanics and the Clinical Treatment of Disease and Injury," Appl. Mech. Rev., vol. 56, No. 2 pp. 231-260 (Mar. 2003). cited by applicant

National Semiconductors Temperature Sensor Handbook—
<http://www.national.com/appinfo/tempsensors/files/temphb.pdf>; accessed online: Apr. 1, 2011. cited by applicant

Hayashi et al., "The Effect of Thermal Heating on the Length and Histologic Properties of the Glenohumeral Joint Capsule," American Journal of Sports Medicine, vol. 25, Issue 1, 11 pages (Jan. 1997), URL: <http://www.mdconsult.com/das/article/body/156183648-2/jorg=journal&source=MI&sp=1> . . . , accessed Aug. 25, 2009. cited by applicant

Douglas, S.C. "Introduction to Adaptive Filter". Digital Signal Processing Handbook. Ed. Vijay K. Madisetti and Douglas B. Williams. Boca Raton: CRC Press LLC, 1999. cited by applicant

Chen et al., "Heat-induced changes in the mechanics of a collagenous tissue: pseudoelastic behavior at 37° C.," Journal of Biomechanics, 31, pp. 211-216 (1998). cited by applicant

Kurt Gieck & Reiner Gieck, *Engineering Formulas* § Z.7 (7th ed. 1997). cited by applicant

Glaser and Subak-Sharpe, Integrated Circuit Engineering, Addison-Wesley Publishing, Reading, MA (1979). (book—not attached). cited by applicant

Wright, et al., "Time-Temperature Equivalence of Heat-Induced Changes in Cells and Proteins," Feb. 1998. ASME Journal of Biomechanical Engineering, vol. 120, pp. 22-26. cited by applicant

Covidien Brochure, [Value Analysis Brief], LigaSure Advance™ Pistol Grip, dated Rev. Apr. 2010

(7 pages). cited by applicant

Covidien Brochure, LigaSure Impact™ Instrument LF4318, dated Feb. 2013 (3 pages). cited by applicant

Covidien Brochure, LigaSure Atlas™ Hand Switching Instruments, dated Dec. 2008 (2 pages). cited by applicant

Covidien Brochure, The LigaSure™ 5 mm Blunt Tip Sealer/Divider Family, dated Apr. 2013 (2 pages). cited by applicant

Jang, J. et al. "Neuro-fuzzy and Soft Computing." Prentice Hall, 1997, pp. 13-89, 199-293, 335-393, 453-496, 535-549. cited by applicant

Sullivan, "Optimal Choice for Number of Strands in a Litz-Wire Transformer Winding," IEEE Transactions on Power Electronics, vol. 14, No. 2, Mar. 1999, pp. 283-291. cited by applicant

Covidien Brochure, The LigaSure Precise™ Instrument, dated Mar. 2011 (2 pages). cited by applicant

<https://www.kjmagnetics.com/fieldcalculator.asp>, retrieved Jul. 11, 2016, backdated to Nov. 11, 2011 via

<https://web.archive.org/web/20111116164447/http://www.kjmagnetics.com/fieldcalculator.asp>. cited by applicant

Leonard I. Malis, M.D., "The Value of Irrigation During Bipolar Coagulation," 1989. cited by applicant

AST Products, Inc., "Principles of Video Contact Angle Analysis," 20 pages, (2006). cited by applicant

Lim et al., "A Review of Mechanism Used in Laparoscopic Surgical Instruments," Mechanism and Machine Theory, vol. 38, pp. 1133-1147, (2003). cited by applicant

F. A. Duck, "Optical Properties of Tissue Including Ultraviolet and Infrared Radiation," pp. 43-71 in Physical Properties of Tissue (1990). cited by applicant

Erbe Electrosurgery VIO® 200 S, (2012), p. 7, 12 pages, accessed Mar. 31, 2014 at http://www.erbe-med.com/erbe/media/Marketing_materialien/85140170_ERBE_EN_VIO_200_S_D027541. cited by applicant

Graff, K.F., "Elastic Wave Propagation in a Curved Sonic Transmission Line," IEEE Transactions on Sonics and Ultrasonics, SU-17(1), 1-6 (1970). cited by applicant

Makarov, S. N., Ochmann, M., Desinger, K., "The longitudinal vibration response of a curved fiber used for laser ultrasound surgical therapy," Journal of the Acoustical Society of America 102, 1191-1199 (1997). cited by applicant

Morley, L. S. D., "Elastic Waves in a Naturally Curved Rod," Quarterly Journal of Mechanics and Applied Mathematics, 14: 155-172 (1961). cited by applicant

Walsh, S. J., White, R. G., "Vibrational Power Transmission in Curved Beams," Journal of Sound and Vibration, 233(3), 455-488 (2000). cited by applicant

Covidien 501 (k) Summary Sonication, dated Feb. 24, 2011 (7 pages). cited by applicant

Gerhard, Glen C., "Surgical Electrotechnology: Quo Vadis?," IEEE Transactions on Biomedical Engineering, vol. BME-31, No. 12, pp. 787-792, Dec. 1984. cited by applicant

Technology Overview, printed from www.harmonicscalpel.com, Internet site, website accessed on Jun. 13, 2007, (3 pages). cited by applicant

Sherrit et al., "Novel Horn Designs for Ultrasonic/Sonic Cleaning Welding, Soldering, Cutting and Drilling," Proc. SPIE Smart Structures Conference, vol. 4701, Paper No. 34, San Diego, CA, pp. 353-360, Mar. 2002. cited by applicant

Gooch et al., "Recommended Infection-Control Practices for Dentistry, 1993," Published: May 28, 1993; [retrieved on Aug. 23, 2008]. Retrieved from the internet: URL: <http://wonder.cdc.gov/wonder/prevguid/p0000191/p0000191.asp> (15 pages). cited by applicant

Huston et al., "Magnetic and Magnetostrictive Properties of Cube Textured Nickel for Magnetostrictive Transducer Applications," IEEE Transactions on Magnetics, vol. 9(4), pp. 636-

640 (Dec. 1973). cited by applicant

Sullivan, “Cost-Constrained Selection of Strand Diameter and Number in a Litz-Wire Transformer Winding,” IEEE Transactions on Power Electronics, vol. 16, No. 2, Mar. 2001, pp. 281-288. cited by applicant

Fowler, K.R., “A Programmable, Arbitrary Waveform Electrosurgical Device,” IEEE Engineering in Medicine and Biology Society 10th Annual International Conference, pp. 1324, 1325 (1988). cited by applicant

LaCourse, J.R.; Vogt, M.C.; Miller, W.T., III; Selikowitz, S.M., “Spectral Analysis Interpretation of Electrosurgical Generator Nerve and Muscle Stimulation,” IEEE Transactions on Biomedical Engineering, vol. 35, No. 7, pp. 505-509, Jul. 1988. cited by applicant

Orr et al., “Overview of Bioheat Transfer,” pp. 367-384 in Optical-Thermal Response of Laser-Irradiated Tissue, A. J. Welch and M. J. C. van Gemert, eds., Plenum, New York (1995). cited by applicant

Campbell et al., “Thermal Imaging in Surgery,” p. 19-3, in Medical Infrared Imaging, N. A. Diakides and J. D. Bronzino, Eds. (2008). cited by applicant

Incropera et al., Fundamentals of Heat and Mass Transfer, Wiley, New York (1990). (Book—not attached). cited by applicant

Hörmann et al., “Reversible and irreversible denaturation of collagen fibers.” Biochemistry, 10, pp. 932-937 (1971). cited by applicant

Dean, D.A., “Electrical Impedance Spectroscopy Study of Biological Tissues,” J. Electrostat, 66(3-4), Mar. 2008, pp. 165-177. Accessed Apr. 10, 2018: <https://www.ncbi.nlm.nih.gov/pmc/articles/PMC2597841/>. cited by applicant

Moraleda et al., A Temperature Sensor Based on a Polymer Optical Fiber Macro-Bend, Sensors 2013, 13, 13076-13089, doi: 10.3390/s131013076, ISSN 1424-8220. cited by applicant

IEEE Std 802.3-2012 (Revision of IEEE Std 802.3-2008, published Dec. 28, 2012. cited by applicant

“ATM-MPLS Network Interworking Version 2.0, af-aic-0178.001” ATM Standard, The ATM Forum Technical Committee, published Aug. 2003. cited by applicant

Missinne, et al. “Stretchable Optical Waveguides,” vol. 22, No. 4, Feb. 18, 2014, pp. 4168-4179 (12 pages). cited by applicant

Primary Examiner: Vahdat; Khadijeh A

Background/Summary

PRIORITY (1) This application is a continuation application claiming priority under 35 U.S.C. § 120 to U.S. patent application Ser. No. 15/382,515, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT AND METHODS THEREFOR, filed on Dec. 16, 2016, published on Jul. 20, 2017 as U.S. Patent Application Publication No. 2017/0202605, and issued on Nov. 24, 2020 as U.S. Pat. No. 10,842,523, which claims the benefit of U.S. Provisional Patent Application No. 62/279,635, titled MODULAR COMBINATION SURGICAL DEVICE, filed Jan. 15, 2016 and U.S. Provisional Patent Application No. 62/330,669, titled MODULAR COMBINATION SURGICAL DEVICE, filed May 2, 2016, the entire disclosures of which are hereby incorporated by reference herein.

BACKGROUND

(1) The present disclosure is related generally to surgical instruments and associated surgical techniques. More particularly, the present disclosure is related to ultrasonic and electrosurgical

systems that allow surgeons to perform cutting and coagulation and to adapt and customize such procedures based on the type of tissue being treated.

(2) Ultrasonic surgical instruments are finding increasingly widespread applications in surgical procedures by virtue of the unique performance characteristics of such instruments. Depending upon specific instrument configurations and operational parameters, ultrasonic surgical instruments can provide simultaneous or near-simultaneous cutting of tissue and hemostasis by coagulation, desirably minimizing patient trauma. The cutting action is typically realized by an end effector, or blade tip, at the distal end of the instrument, which transmits ultrasonic energy to tissue brought into contact with the end effector. Ultrasonic instruments of this nature can be configured for open surgical use, laparoscopic, or endoscopic surgical procedures including robotic-assisted procedures.

(3) Some surgical instruments utilize ultrasonic energy for both precise cutting and controlled coagulation. Ultrasonic energy cuts and coagulates by vibrating a blade in contact with tissue. Vibrating at high frequencies (e.g., 55,500 times per second), the ultrasonic blade denatures protein in the tissue to form a sticky coagulum. Pressure exerted on tissue with the blade surface collapses blood vessels and allows the coagulum to form a hemostatic seal. The precision of cutting and coagulation is controlled by the surgeon's technique and adjusting the power level, blade edge, tissue traction, and blade pressure.

(4) Electrosurgical instruments for applying electrical energy to tissue in order to treat and/or destroy the tissue are also finding increasingly widespread applications in surgical procedures. An electrosurgical instrument typically includes a hand piece, an instrument having a distally-mounted end effector (e.g., one or more electrodes). The end effector can be positioned against the tissue such that electrical current is introduced into the tissue. Electrosurgical instruments can be configured for bipolar or monopolar operation. During bipolar operation, current is introduced into and returned from the tissue by active and return electrodes, respectively, of the end effector. During monopolar operation, current is introduced into the tissue by an active electrode of the end effector and returned through a return electrode (e.g., a grounding pad) separately located on a patient's body. Heat generated by the current flowing through the tissue may form hemostatic seals within the tissue and/or between tissues and thus may be particularly useful for sealing blood vessels, for example. The end effector of an electrosurgical instrument also may include a cutting member that is movable relative to the tissue and the electrodes to transect the tissue.

(5) Electrical energy applied by an electrosurgical instrument can be transmitted to the instrument by a generator in communication with the hand piece. The electrical energy may be in the form of radio frequency ("RF") energy. RF energy is a form of electrical energy that may be in the frequency range of 200 kilohertz (kHz) to 1 megahertz (MHz). In application, an electrosurgical instrument can transmit low frequency RF energy through tissue, which causes ionic agitation, or friction, in effect resistive heating, thereby increasing the temperature of the tissue. Because a sharp boundary is created between the affected tissue and the surrounding tissue, surgeons can operate with a high level of precision and control, without sacrificing un-targeted adjacent tissue. The low operating temperatures of RF energy is useful for removing, shrinking, or sculpting soft tissue while simultaneously sealing blood vessels. RF energy works particularly well on connective tissue, which is primarily comprised of collagen and shrinks when contacted by heat.

(6) The RF energy may be in a frequency range described in EN 60601-2-2:2009+A11:2011, Definition 201.3.218—HIGH FREQUENCY. For example, the frequency in monopolar RF applications may be typically restricted to less than 5 MHz. However, in bipolar RF applications, the frequency can be almost anything. Frequencies above 200 kHz can be typically used for monopolar applications in order to avoid the unwanted stimulation of nerves and muscles that would result from the use of low frequency current. Lower frequencies may be used for bipolar applications if the risk analysis shows the possibility of neuromuscular stimulation has been mitigated to an acceptable level. Normally, frequencies above 5 MHz are not used in order to minimize the problems associated with high frequency leakage currents. Higher frequencies may,

however, be used in the case of bipolar applications. It is generally recognized that 10 mA is the lower threshold of thermal effects on tissue.

(7) A challenge of using these medical devices is the inability to fully control and customize the functions of the surgical instruments. It would be desirable to provide a surgical instrument that overcomes some of the deficiencies of current instruments.

SUMMARY

(8) In one aspect, the present disclosure provides a method of controlling a modular battery powered handheld surgical instrument. The surgical instrument comprising a battery, a user input sensor, a controller, a radio frequency (RF) drive circuit, an ultrasonic transducer, ultrasonic transducer drive circuit, and an end effector. The end effector comprising an electrode electrically coupled to RF drive circuit, an ultrasonic blade acoustically coupled to the ultrasonic transducer, and a sensor to measure tissue parameters. The method comprising applying an RF current drive signal to the electrode by the RF drive circuit; applying an ultrasonic drive signal to the ultrasonic transducer by the ultrasonic transducer drive circuit to acoustically excite the ultrasonic blade; controlling intensity, wave shape, and/or frequency of the RF current drive signal based on a sensed measure of a tissue or user parameter.

(9) In another aspect, the present disclosure provides a method of controlling a modular battery powered handheld surgical instrument. The surgical instrument comprising a battery, a user input sensor, a controller, a radio frequency (RF) drive circuit, an ultrasonic transducer, ultrasonic transducer drive circuit, and an end effector. The end effector comprising an electrode electrically coupled to RF drive circuit, an ultrasonic blade acoustically coupled to the ultrasonic transducer, and a sensor to measure tissue parameters. The method comprising applying an RF current drive signal to the electrode by the RF drive circuit; applying an ultrasonic drive signal to the ultrasonic transducer by the ultrasonic transducer drive circuit to acoustically excite the ultrasonic blade; controlling intensity, wave shape, and/or frequency of the ultrasonic drive signal based on a tissue or user parameter.

(10) In another aspect, the present disclosure provides a method of controlling a modular battery powered handheld surgical instrument. The surgical instrument comprising a battery, a user input sensor, a controller, a radio frequency (RF) drive circuit, an ultrasonic transducer, ultrasonic transducer drive circuit, and an end effector. The end effector comprising an electrode electrically coupled to RF drive circuit, an ultrasonic blade acoustically coupled to the ultrasonic transducer, and a sensor to measure tissue parameters. The method comprising applying an RF current drive signal to the electrode by the RF drive circuit; applying an ultrasonic drive signal to the ultrasonic transducer by the ultrasonic transducer drive circuit to acoustically excite the ultrasonic blade; controlling intensity, wave shape, and/or frequency of the RF current drive signal and the ultrasonic drive signal on a sensed measure of a tissue or user parameter.

(11) In addition to the foregoing, various other method and/or system and/or program product aspects are set forth and described in the teachings such as text (e.g., claims and/or detailed description) and/or drawings of the present disclosure.

(12) The foregoing is a summary and thus may contain simplifications, generalizations, inclusions, and/or omissions of detail; consequently, those skilled in the art will appreciate that the summary is illustrative only and is NOT intended to be in any way limiting. Other aspects, features, and advantages of the devices and/or processes and/or other subject matter described herein will become apparent in the teachings set forth herein.

(13) In one or more various aspects, related systems include but are not limited to circuitry and/or programming for effecting herein-referenced method aspects; the circuitry and/or programming can be virtually any combination of hardware, software, and/or firmware configured to affect the herein-referenced method aspects depending upon the design choices of the system designer. In addition to the foregoing, various other method and/or system aspects are set forth and described in the teachings such as text (e.g., claims and/or detailed description) and/or drawings of the present

disclosure.

(14) Further, it is understood that any one or more of the following-described forms, expressions of forms, examples, can be combined with any one or more of the other following-described forms, expressions of forms, and examples.

(15) The foregoing summary is illustrative only and is not intended to be in any way limiting. In addition to the illustrative aspects, and features described above, further aspects, and features will become apparent by reference to the drawings and the following detailed description.

Description

FIGURES

(1) The novel features of the various aspects described herein are set forth with particularity in the appended claims. The various aspects, however, both as to organization and methods of operation may be better understood by reference to the following description, taken in conjunction with the accompanying drawings as follows:

(2) FIG. 1 is a diagram of a modular battery powered handheld ultrasonic surgical instrument, according to an aspect of the present disclosure.

(3) FIG. 2 is an exploded view of the surgical instrument shown in FIG. 1, according to an aspect of the present disclosure.

(4) FIG. 3 is an exploded view of a modular shaft assembly of the surgical instrument shown in FIG. 1, according to aspect of the present disclosure.

(5) FIG. 4 is a perspective transparent view of the ultrasonic transducer/generator assembly of the surgical instrument shown in FIG. 1, according to aspect of the present disclosure.

(6) FIG. 5 is an end view of the ultrasonic transducer/generator assembly, according to aspect of the present disclosure.

(7) FIG. 6 is a perspective view of the ultrasonic transducer/generator assembly with the top housing portion removed to expose the ultrasonic generator, according to aspect of the present disclosure.

(8) FIG. 7 is a sectional view of the of the ultrasonic transducer/generator assembly, according to aspect of the present disclosure.

(9) FIG. 8 is an elevation view of an ultrasonic transducer/generator assembly that is configured to operate at 31 kHz resonant frequency, according to one aspect of the present disclosure.

(10) FIG. 9 is an elevation view of an ultrasonic transducer/generator assembly that is configured to operate at 55 kHz resonant frequency, according to one aspect of the present disclosure.

(11) FIGS. 10A and 10B illustrate a shifting assembly that selectively rotates the ultrasonic transmission waveguide with respect to the ultrasonic transducer and urges them towards one another, according to one aspect of the present disclosure.

(12) FIG. 11 is a schematic diagram of one aspect of an ultrasonic drive circuit shown in FIG. 4 suitable for driving an ultrasonic transducer, according to one aspect of the present disclosure.

(13) FIG. 12 is a schematic diagram of the transformer coupled to the ultrasonic drive circuit shown in FIG. 11, according to one aspect of the present disclosure.

(14) FIG. 13 is a schematic diagram of the transformer shown in FIG. 12 coupled to a test circuit, according to one aspect of the present disclosure.

(15) FIG. 14 is a schematic diagram of a control circuit, according to one aspect f the present disclosure.

(16) FIG. 15 shows a simplified block circuit diagram illustrating another electrical circuit contained within a modular ultrasonic surgical instrument, according to one aspect of the present disclosure.

(17) FIG. 16 shows a battery assembly for use with the surgical instrument, according to one aspect

of the present disclosure.

(18) FIG. **17** shows a disposable battery assembly for use with the surgical instrument, according to one aspect of the present disclosure.

(19) FIG. **18** shows a reusable battery assembly for use with the surgical instrument, according to one aspect of the present disclosure.

(20) FIG. **19** is an elevated perspective view of a battery assembly with both halves of the housing shell removed exposing battery cells coupled to multiple circuit boards which are coupled to the multi-lead battery terminal in accordance with one aspect of the present disclosure.

(21) FIG. **20** illustrates a battery test circuit, according to one aspect of the present disclosure.

(22) FIG. **21** illustrates a supplemental power source circuit to maintain a minimum output voltage, according to one aspect of the present disclosure.

(23) FIG. **22** illustrates a switch mode power supply circuit for supplying energy to the surgical instrument, according to one aspect of the present disclosure.

(24) FIG. **23** illustrates a discrete version of the switching regulator shown in FIG. **22** for supplying energy to the surgical instrument, according to one aspect of the present disclosure.

(25) FIG. **24** illustrates a linear power supply circuit for supplying energy to the surgical instrument, according to one aspect of the present disclosure.

(26) FIG. **25** is an elevational exploded view of modular handheld ultrasonic surgical instrument showing the left shell half removed from a handle assembly exposing a device identifier communicatively coupled to the multi-lead handle terminal assembly in accordance with one aspect of the present disclosure.

(27) FIG. **26** is a detail view of a trigger portion and switch of the ultrasonic surgical instrument shown in FIG. **25**, according to one aspect of the present disclosure.

(28) FIG. **27** is a fragmentary, enlarged perspective view of an end effector from a distal end with a jaw member in an open position, according to one aspect of the present disclosure.

(29) FIG. **28** illustrates a modular shaft assembly and end effector portions of the surgical instrument, according to one aspect of the present disclosure.

(30) FIG. **29** is a detail view of an inner tube/spring assembly, according to one aspect of present disclosure.

(31) FIG. **30** illustrates a modular battery powered handheld combination ultrasonic/electrosurgical instrument, according to one aspect of the present disclosure.

(32) FIG. **31** is an exploded view of the surgical instrument shown in FIG. **30**, according to one aspect of the present disclosure.

(33) FIG. **32** is a partial perspective view of a modular battery powered handheld combination ultrasonic/RF surgical instrument, according to one aspect of the present disclosure.

(34) FIG. **33** illustrates a nozzle portion of the surgical instruments described in connection with FIGS. **30-32**, according to one aspect of the present disclosure.

(35) FIG. **34** is a schematic diagram of one aspect of a drive circuit configured for driving a high-frequency current (RF), according to one aspect of the present disclosure.

(36) FIG. **35** is a schematic diagram of the transformer coupled to the RF drive circuit shown in FIG. **34**, according to one aspect of the present disclosure.

(37) FIG. **36** is a schematic diagram of a circuit comprising separate power sources for high power energy/drive circuits and low power circuits, according to one aspect of the resent disclosure.

(38) FIG. **37** illustrates a control circuit that allows a dual generator system to switch between the RF generator and the ultrasonic generator energy modalities for the surgical instrument shown in FIGS. **30** and **31**.

(39) FIG. **38** is a sectional view of an end effector, according to one aspect of the present disclosure.

(40) FIG. **39** is a sectional view of an end effector, according to one aspect of the present disclosure.

(41) FIG. 40 is a partial longitudinal sectional side view showing a distal jaw section in a closed state, according to one aspect of the present disclosure.

(42) FIG. 41 is a partial longitudinal sectional side view showing the distal jaw section in an open state, according to one aspect of the present disclosure.

(43) FIG. 42 is a partial longitudinal sectional side view showing a jaw member, according to one aspect of the present disclosure.

(44) FIG. 43 is a cross-sectional view showing the distal jaw section in a normal state, according to one aspect of the present disclosure.

(45) FIG. 44 is a cross-sectional view showing the distal jaw section in a worn state, according to one aspect of the present disclosure.

(46) FIG. 45 illustrates a modular battery powered handheld electrosurgical instrument with distal articulation, according to one aspect of the present disclosure.

(47) FIG. 46 is an exploded view of the surgical instrument shown in FIG. 45, according to one aspect of the present disclosure.

(48) FIG. 47 is a perspective view of the surgical instrument shown in FIGS. 45 and 46 with a display located on the handle assembly, according to one aspect of the present disclosure.

(49) FIG. 48 is a perspective view of the instrument shown in FIGS. 45 and 46 without a display located on the handle assembly, according to one aspect of the present disclosure.

(50) FIG. 49 is a motor assembly that can be used with the surgical instrument to drive the knife, according to one aspect of the present disclosure.

(51) FIG. 50 is diagram of a motor drive circuit, according to one aspect of the present disclosure.

(52) FIG. 51 illustrates a rotary drive mechanism to drive distal head rotation, articulation, and jaw closure, according to one aspect of the present disclosure.

(53) FIG. 52 is an enlarged, left perspective view of an end effector assembly with the jaw members shown in an open configuration, according to one aspect of the present disclosure.

(54) FIG. 53 is an enlarged, right side view of the end effector assembly of FIG. 52, according to one aspect of the present disclosure.

(55) FIG. 54 illustrates a modular battery powered handheld electrosurgical instrument with distal articulation, according to one aspect of the present disclosure.

(56) FIG. 55 is an exploded view of the surgical instrument shown in FIG. 54, according to one aspect of the present disclosure.

(57) FIG. 56 is an enlarged area detail view of an articulation section illustrated in FIG. 54 including electrical connections, according to one aspect of the present disclosure.

(58) FIG. 57 is an enlarged area detail view articulation section illustrated in FIG. 56 including electrical connections, according to one aspect of the present disclosure.

(59) FIG. 58 illustrates a perspective view of components of the shaft assembly, end effector, and cutting member of the surgical instrument of FIG. 54, according to one aspect of the present disclosure.

(60) FIG. 59 illustrates the articulation section in a second stage of articulation, according to one aspect of the present disclosure.

(61) FIG. 60 illustrates a perspective view of the end effector of the device of FIGS. 54-59 in an open configuration, according to one aspect of the present disclosure.

(62) FIG. 61 illustrates a cross-sectional end view of the end effector of FIG. 60 in a closed configuration and with the blade in a distal position, according to one aspect to the present disclosure.

(63) FIG. 62 illustrates the components of a control circuit of the surgical instrument, according to one aspect of the present disclosure.

(64) FIG. 63 is a system diagram of a segmented circuit comprising a plurality of independently operated circuit segments, according to one aspect of the present disclosure. FIG. 63 is a diagram of one form of a direct digital synthesis circuit.

(65) FIG. **64** illustrates a diagram of one aspect of a surgical instrument comprising a feedback system for use with any one of the surgical instruments described herein in connection with FIGS. **1-61**, which may include or implement many of the features described herein

(66) FIG. **65** illustrates one aspect of a fundamental architecture for a digital synthesis circuit such as a direct digital synthesis (DDS) circuit configured to generate a plurality of wave shapes for the electrical signal waveform for use in any of the surgical instruments described herein in connection with FIGS. **1-61**, according to one aspect of the present disclosure.

(67) FIG. **66** illustrates one aspect of direct digital synthesis (DDS) circuit configured to generate a plurality of wave shapes for the electrical signal waveform for use in any of the surgical instruments described herein in connection with FIGS. **1-61**, according to one aspect of the present disclosure.

(68) FIG. **67** illustrates one cycle of a discrete time digital electrical signal waveform, according to one aspect of the present disclosure of an analog waveform (shown superimposed over a discrete time digital electrical signal waveform for comparison purposes), according to one aspect of the present disclosure.

(69) FIG. **68A** illustrates a circuit comprising a controller comprising one or more processors coupled to at least one memory circuit for use in any of the surgical instruments described herein in connection with FIGS. **1-61**, according to one aspect of the present disclosure.

(70) FIG. **68B** illustrates a circuit comprising a finite state machine comprising a combinational logic circuit configured to implement any of the algorithms, processes, or techniques described herein, according to one aspect of the present disclosure.

(71) FIG. **68C** illustrates a circuit comprising a finite state machine comprising a sequential logic circuit configured to implement any of the algorithms, processes, or techniques described herein, according to one aspect of the present disclosure.

(72) FIG. **69** is a circuit diagram of various components of a surgical instrument with motor control functions, according to one aspect of the present disclosure.

(73) FIG. **70** illustrates a handle assembly with a removable service panel removed to shown internal components of the handle assembly, according to one aspect of the present disclosure.

(74) FIG. **71** is a graphical representation of determining wait time based on tissue thickness, according to aspects of the present disclosure.

(75) FIG. **72** is a force versus time graph for thin, medium, and thick tissue types, according to aspects of the present disclosure.

(76) FIG. **73** is a graph of motor current versus time for different tissue types, according to aspects of the present disclosure.

(77) FIG. **74** is a graphical depiction of impedance bath tub, according to aspects of the present disclosure.

(78) FIG. **75** is a graph depicting one aspect of adjustment of energy switching threshold due to the measurement of a secondary tissue parameter, according to aspects of the present disclosure.

(79) FIG. **76** is a diagram of a process illustrating selective application of radio frequency or ultrasonic treatment energy based on measured tissue characteristics, according to aspects of the present disclosure.

(80) FIG. **77** is a graph depicting a relationship between trigger button displacement and sensor output, according to aspects of the present disclosure.

(81) FIG. **78** is a graph depicting an abnormal relationship between trigger button displacement and sensor output, according to aspects of the present disclosure.

(82) FIG. **79** is a graph depicting an acceptable relationship between trigger button displacement and sensor output, according to aspects of the present disclosure.

(83) FIG. **80** illustrates one aspect of a left-right segmented flexible circuit, according to aspects of the present disclosure.

(84) FIG. **81** is a cross-sectional view of one aspect of a flexible circuit comprising RF electrodes

and data sensors embedded therein, according to aspects of the present disclosure.

(85) FIG. **82** is a cross sectional view of an end effector comprising a jaw member, a flexible circuit, and a segmented electrode, according to one aspect of the present disclosure.

(86) FIG. **83** is a detailed view of the end effector shown in FIG. **82**, according to one aspect of the present disclosure.

(87) FIG. **84A** is a cross sectional view of an end effector comprising a rotatable jaw member, a flexible circuit, and an ultrasonic blade positioned in a vertical orientation relative to the jaw member with no tissue located between the jaw member and the ultrasonic blade, according to one aspect of the present disclosure.

(88) FIG. **84B** is a cross sectional view of the end effector shown in FIG. **84A** with tissue located between the jaw member and the ultrasonic blade, according to one aspect of the present disclosure.

(89) FIG. **85A** is a cross sectional view of the effector shown in FIGS. **84A** and **84B** with the ultrasonic blade positioned in a horizontal orientation relative to the jaw member with no tissue located between the jaw member and the ultrasonic blade, according to one aspect of the present disclosure.

(90) FIG. **85B** is a cross sectional view of the end effector shown in FIG. **85A** with tissue located between the jaw member and the ultrasonic blade, according to one aspect of the present disclosure.

(91) FIG. **86** illustrates one aspect of an end effector comprising RF data sensors located on the jaw member, according to one aspect of the present disclosure.

(92) FIG. **87** illustrates one aspect of the flexible circuit shown in FIG. **86** in which the sensors may be mounted to or formed integrally therewith, according to one aspect of the present disclosure.

(93) FIG. **88** is a cross-sectional view of the flexible circuit shown in FIG. **87**, according to one aspect of the present disclosure.

(94) FIG. **89** illustrates one aspect of a segmented flexible circuit configured to fixedly attach to a jaw member of an end effector, according to one aspect of the present disclosure.

(95) FIG. **90** illustrates one aspect of a segmented flexible circuit configured to mount to a jaw member of an end effector, according to one aspect of the present disclosure.

(96) FIG. **91** illustrates one aspect of an end effector configured to measure a tissue gap GT, according to one aspect of the present disclosure.

(97) FIG. **92** illustrates one aspect of an end effector comprising segmented flexible circuit, according to one aspect of the present disclosure.

(98) FIG. **93** illustrates the end effector shown in FIG. **92** with the jaw member clamping tissue between the jaw member and the ultrasonic blade, according to one aspect of the present disclosure.

(99) FIG. **94** illustrates graphs of energy applied by the right and left side of an end effector based on locally sensed tissue parameters, according to one aspect of the present disclosure.

(100) FIG. **95** is a cross-sectional view of one aspect of an end effector configured to sense force or pressure applied to tissue located between a jaw member and an ultrasonic blade, according to one aspect of the present disclosure.

(101) FIG. **96** is a schematic diagram of one aspect of a signal layer of a flexible circuit, according to one aspect of the present disclosure.

(102) FIG. **97** is a schematic diagram of sensor wiring for the flexible circuit shown in FIG. **96**, according to one aspect of the present disclosure.

(103) FIG. **98A** is a graphical representation of one aspect of a medical device surrounding tissue, according to one aspect of the present disclosure.

(104) FIG. **98B** is a graphical representation of one aspect of a medical device compressing tissue, according to one aspect of the present disclosure.

(105) FIG. **99A** is a graphical representation of one aspect of a medical device compressing tissue,

according to one aspect of the present disclosure.

(106) FIG. **99B** also depicts example forces exerted by one aspect of an end-effector of a medical device compressing tissue, according to one aspect of the present disclosure.

(107) FIG. **100** illustrates a logic diagram of one aspect of a feedback system, according to one aspect of the present disclosure.

(108) FIG. **101** is a graph showing a limiting operation on a torque applied to a transducer;

(109) FIG. **102** is a graph comparing different limiting conditions and different limiting operations when the motor is driving different moving components, according to one aspect of the present disclosure.

(110) FIG. **103** is a perspective view of a motor comprising a strain gauge used for measuring torque, according to one aspect of the present disclosure.

(111) FIG. **104** are graphs and showing smoothing out of fine trigger button movement by a motor controller, according to one aspect of the present disclosure.

(112) FIG. **105** is a graph showing a non-linear force limit and corresponding velocity adjustment for I-blade RF motor control, according to one aspect of the present disclosure.

(113) FIG. **106** is a graph showing force limits and corresponding velocity adjustments for jaw motor control, according to one aspect of the present disclosure.

(114) FIG. **107** are graphs showing different velocity limits when the motor is driving different moving components, according to one aspect of the present disclosure.

(115) FIG. **108** is a graph showing velocity limits at the beginning and the end of the range of movement, according to one aspect of the present disclosure.

(116) FIG. **109** are diagrams showing velocity limits at the beginning and the end of the range of movement for jaw clamping and I-beam advance, according to one aspect of the present disclosure.

(117) FIG. **110** are diagrams showing measurement of out-of-phase aspect of the current through the motor, according to one aspect of the present disclosure.

(118) FIG. **111** is a graph showing adjustment of velocity limit based on tissue type, according to one aspect of the present disclosure.

(119) FIG. **112** is a graph showing different wait periods and different velocity limits in I-beam motor control for tissues with different thickness, according to one aspect of the present disclosure.

(120) FIG. **113** are graphs depicting a relationship between trigger button displacement and sensor output, according to one aspect of the present disclosure.

(121) FIG. **114** illustrates an elevation view of system comprising a modular ultrasonic transducer assembly attached to a modular handle assembly of a battery powered modular handheld surgical instrument, wherein an ultrasonic waveguide of a modular shaft assembly is positioned for attachment to an ultrasonic transducer shaft of the modular ultrasonic transducer assembly according to an aspect of the present disclosure.

(122) FIG. **115** illustrates an elevation view of the system of FIG. **114**, wherein the ultrasonic waveguide is positioned in axial alignment with the ultrasonic transducer shaft when the modular shaft assembly is attached to the modular ultrasonic transducer assembly and the modular handle assembly of the battery powered modular handheld surgical instrument according to an aspect of the present disclosure.

(123) FIG. **116** illustrates an elevation view of the system of FIG. **114**, wherein the ultrasonic waveguide of the modular shaft assembly is attached to and torqued to the ultrasonic transducer shaft of the modular ultrasonic transducer assembly according to an aspect of the present disclosure.

(124) FIG. **117** illustrates an elevation view of a modular handheld surgical instrument wherein a shifting spur gear has been translated from a first position at a primary drive gear to a second position at a slip clutch gear for a primary gear of a motor to rotate the slip-clutch gear via the shifting spur gear according to an aspect of the present disclosure.

(125) FIG. **118** illustrates an isometric view of a portion of the modular handheld surgical

instrument of FIG. **117**, wherein the ultrasonic waveguide is rotatable within a primary rotary drive rotatable via the primary drive gear within an exterior shaft rotatable via a slip clutch subsystem of the slip clutch gear according to an aspect of the present disclosure.

(126) FIG. **119** illustrates an elevation view of a portion of the modular handheld surgical instrument of FIG. **117**, wherein the exterior shaft is coupled to the ultrasonic waveguide and wherein the exterior shaft is coupleable to a fixed external housing of the modular handheld surgical instrument according to an aspect of the present disclosure.

(127) FIG. **120** illustrates a top elevation view of the system of FIG. **114** comprising a transducer locking mechanism to lock the ultrasonic transducer of the modular ultrasonic transducer assembly according to an aspect of the present disclosure.

(128) FIG. **121** illustrates an end elevation view of the system of FIG. **114** that shows the slip clutch subsystem of FIG. **118** and the transducer locking mechanism of FIG. **120** according to an aspect of the present disclosure.

(129) FIG. **122** illustrates a top elevation view of the transducer locking mechanism of FIG. **120** being operated via a torque lever to lock the ultrasonic transducer of the modular ultrasonic transducer assembly according to an aspect of the present disclosure.

(130) FIG. **123** illustrates a graph of torque versus motor current wherein current supplied to the motor is electronically limited when torqueing the ultrasonic waveguide of the modular shaft assembly onto the ultrasonic transducer shaft of the modular ultrasonic transducer assembly according to an aspect of the present disclosure.

(131) FIG. **124** illustrates graphs of torque versus motor current wherein current supplied to the motor is electronically limited based on the function (e.g., torqueing, rotating, articulating, clamping, etc.) performed by the modular handheld surgical instrument according to an aspect of the present disclosure.

(132) FIG. **125** illustrates an isometric view of a motor of the modular handheld surgical instrument wherein a strain gauge is used to measure torque applied by the motor according to an aspect of the present disclosure.

(133) FIG. **126** is a system schematic diagram illustrating components of a battery powered modular surgical instrument, such as the battery operated modular surgical instruments described herein in connection with FIGS. **1-70**, according to various aspects of the present disclosure.

(134) FIG. **127** describes a distribution of pluralities of control programs according to one aspect of the present disclosure in which the memory device of the control handle assembly stores a plurality of control programs comprising base operating control programs corresponding to the general operation of the modular surgical instrument, according to one aspect of the present disclosure.

(135) FIG. **128** describes a distribution of pluralities of control programs according to one aspect of the present disclosure in which the memory device of the battery assembly stores a plurality of control programs comprising base operating control programs corresponding to the general operation of the modular surgical instrument, according to an aspect of the present disclosure.

(136) FIG. **129** describes a distribution of pluralities of control programs according to one aspect of the present disclosure in which the memory device stores a plurality of control programs comprising base operating control programs corresponding to the general operation of the modular surgical instrument, according to one aspect of the present disclosure.

(137) FIG. **130** is a logic diagram of a process for controlling the operation of a battery assembly operated modular surgical instrument with a plurality of control programs, according to one aspect of the present disclosure.

(138) FIG. **131** is a logic diagram of a process for controlling the operation of a battery assembly operated modular surgical instrument with a plurality of control programs, according to one aspect of the present disclosure.

(139) FIG. **132** is a logic diagram of a process for controlling the operation of a surgical instrument according to the energy conservation method comprising the POST and operation verification,

according to one aspect of the present disclosure.

(140) FIG. **133** is a logic diagram of a process for controlling the operation of a surgical instrument according to the energy conservation method comprising a deenergization sequence and an energization sequence, according to one aspect of the present disclosure.

(141) FIG. **134** illustrates a control circuit for selecting a segmented circuit of a surgical instrument, according to an aspect of the present disclosure.

(142) FIG. **135** is a logic diagram of a process for controlling the operation of a surgical instrument according to the energy conservation method comprising a deenergization sequence and an energization sequence that is different from the deenergization sequence, according to one aspect of the present disclosure.

(143) FIG. **136** illustrates a generator circuit partitioned into multiple stages, according to one aspect of the present disclosure.

(144) FIG. **137** illustrates a generator circuit partitioned into multiple stages where a first stage circuit is common to the second stage circuit, according to one aspect of the present disclosure.

(145) FIG. **138** shows an example system of shaft control electronics interconnecting inside a portion of a handle assembly and shaft assembly of a medical device, according to one aspect of the present disclosure.

(146) FIG. **139** provides an example of a zoomed in portion of the flexible circuit, according to some aspects, according to one aspect of the present disclosure.

(147) FIGS. **140A** and **140B** show how a plurality of sensors may be used in combination to measure and monitor movements of the medical device, according to one aspect of the present disclosure.

(148) FIG. **141** provides another example of how multiple sensors can be used to determine a three-dimensional position of one or more magnets, according to one aspect of the present disclosure.

(149) FIG. **142** shows a variation of a shaft assembly of a medical device that includes a seal to protect sensitive electronics, according to one aspect of the present disclosure.

(150) FIG. **143** shows the inner workings of a portion of a shaft assembly that is part of the surgical instrument and includes multiple clutch systems, according to one aspect of the present disclosure.

(151) FIGS. **144A**, **144B**, **144C**, **144D**, **144E**, and **144F** show another variation for including multiple clutch systems, according to one aspect of the present disclosure.

(152) FIGS. **145A** and **145B** show a shaft assembly that may include a locking element to help stabilize engagement of the clutches, according to one aspect of the present disclosure.

(153) FIGS. **146A** and **146B** show side views of the locking element, according to one aspect of the present disclosure.

(154) FIG. **147** shows an example plot of the amount of voltage output by a power switch in relation to its sliding distance within a slot of a self diagnosing control switch, according to one aspect of the present disclosure.

(155) FIG. **148** provides an example of how the displacement vs. voltage profile of a control switch may change over time, due to natural wear and tear of the mechanical and electrical components, according to one aspect of the present disclosure.

(156) FIG. **149** shows how the self diagnosing control switch of the present disclosures may be configured to transmit an alert when it is determined that automatic adjustments to account for wear and tear are no longer possible, according to one aspect of the present disclosure.

(157) FIG. **150** is a side elevational view of one aspect of a handle assembly of a battery powered modular surgical instrument, according to one aspect of the present disclosure.

(158) FIG. **151** is a side elevational view of another aspect of a handle assembly of a battery powered modular surgical instrument, according to one aspect of the present disclosure.

(159) FIG. **152** is a side elevational view of another aspect of a handle assembly of a battery powered modular surgical instrument, according to one aspect of the present disclosure.

(160) FIG. **153A** illustrates a cross sectional view of a reusable and serviceable handle assembly

with a service cover in an open position, according to one aspect of the present disclosure.

(161) FIG. **153B** illustrates a cross sectional view of the reusable and serviceable handle assembly shown in FIG. **153A** with the service cover in a closed position, according to one aspect of the present disclosure.

(162) FIG. **154A** illustrates a cross sectional view of a reusable and serviceable handle assembly with a service cover in an open position, according to one aspect of the present disclosure.

(163) FIG. **154B** illustrates a cross sectional view of the reusable and serviceable handle assembly shown in FIG. **154A** with the service cover in a closed position, according to one aspect of the present disclosure.

(164) FIG. **155A** illustrates a handle assembly in a secure fastened configuration, according to one aspect of the present disclosure.

(165) FIG. **155B** illustrates the handle assembly shown in FIG. **155A** in an unlatched configuration, according to one aspect of the present disclosure.

(166) FIG. **156** is a plan view of one aspect of an end effector, according to one aspect of the present disclosure.

(167) FIG. **157** is a side view of the end effector shown in FIG. **156** with a partial cut away view to expose the underlying structure of the jaw member and an ultrasonic blade, according to one aspect of the present disclosure.

(168) FIG. **158** is a partial sectional view of the end effector shown in FIGS. **156**, **157** to expose the ultrasonic blade and right and left electrodes, respectively, according to one aspect of the present disclosure.

(169) FIG. **159** is a cross-sectional view taken at section **174-174** of the end effector shown in FIG. **156**, according to one aspect of the present disclosure.

(170) FIG. **160** is a cross-sectional view taken at section **175-175** of the end effector shown in FIG. **156**, according to one aspect of the present disclosure.

(171) FIG. **161** is a cross-sectional view taken at section **174-174** of the end effector shown in FIG. **156**, except that the ultrasonic blade has a different geometric configuration, according to one aspect of the present disclosure.

(172) FIG. **162** is a cross-sectional view taken at section **175-175** of the end effector shown in FIG. **156**, except that the ultrasonic blade has a different geometric configuration, according to one aspect of the present disclosure.

(173) FIG. **163** is a cross-sectional view taken at section **174-174** of the end effector shown in FIG. **156**, except that the ultrasonic blade has a different geometric configuration, according to one aspect of the present disclosure.

(174) FIG. **164** is a cross-sectional view taken at section **175-175** of the end effector shown in FIG. **156**, except that the ultrasonic blade has a different geometric configuration, according to one aspect of the present disclosure.

(175) FIG. **165** illustrates a logic diagram of one aspect of a feedback system, according to one aspect of the present disclosure.

DESCRIPTION

(176) This application is related to following commonly owned patent applications filed on Dec. 16, 2016, the content of each of which is incorporated herein by reference in its entirety:

(177) U.S. patent application Ser. No. 15/382,238, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH SELECTIVE APPLICATION OF ENERGY BASED ON TISSUE CHARACTERIZATION, now U.S. Patent Application Publication No. 2017/0202591.

(178) U.S. patent application Ser. No. 15/382,246, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH SELECTIVE APPLICATION OF ENERGY BASED ON BUTTON DISPLACEMENT, INTENSITY, OR LOCAL TISSUE CHARACTERIZATION, now U.S. Patent Application Publication No. 2017/0202607.

- (179) U.S. patent application Ser. No. 15/382,252, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH VARIABLE MOTOR CONTROL LIMITS, now U.S. Pat. No. 10,537,351.
- (180) U.S. patent application Ser. No. 15/382,257, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH MOTOR CONTROL LIMIT PROFILE, now U.S. Pat. No. 10,299,821.
- (181) U.S. patent application Ser. No. 15/382,265, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH MOTOR CONTROL LIMITS BASED ON TISSUE CHARACTERIZATION, now U.S. Patent Application Publication No. 2017/0202594.
- (182) U.S. patent application Ser. No. 15/382,274, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH MULTI-FUNCTION MOTOR VIA SHIFTING GEAR ASSEMBLY, now U.S. Pat. No. 10,251,664.
- (183) U.S. patent application Ser. No. 15/382,281, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH A PLURALITY OF CONTROL PROGRAMS, now U.S. Patent Application Publication No. 2017/0202595.
- (184) U.S. patent application Ser. No. 15/382,283, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH ENERGY CONSERVATION TECHNIQUES, now U.S. Patent Application Publication No. 2017/0202596.
- (185) U.S. patent application Ser. No. 15/382,285, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH VOLTAGE SAG RESISTANT BATTERY PACK, now U.S. Patent Application Publication No. 2017/0207467.
- (186) U.S. patent application Ser. No. 15/382,287, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH MULTISTAGE GENERATOR CIRCUITS, now U.S. Patent Application Publication No. 2017/0202597.
- (187) U.S. patent application Ser. No. 15/382,288, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH MULTIPLE MAGNETIC POSITION SENSORS, now U.S. Patent Application Publication No. 2017/0202598.
- (188) U.S. patent application Ser. No. 15/382,290, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT CONTAINING ELONGATED MULTI-LAYERED SHAFT, now U.S. Patent Application Publication No. 2017/0202608.
- (189) U.S. patent application Ser. No. 15/382,292, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH MOTOR DRIVE, now U.S. Patent Application Publication No. 2017/0202572.
- (190) U.S. patent application Ser. No. 15/382,297, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH SELF-DIAGNOSING CONTROL SWITCHES FOR REUSABLE HANDLE ASSEMBLY, now U.S. Patent Application Publication No. 2017/0202599.
- (191) U.S. patent application Ser. No. 15/382,306, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH REUSABLE ASYMMETRIC HANDLE HOUSING, now U.S. Patent Application Publication No. 2017/0202571.
- (192) U.S. patent application Ser. No. 15/382,309, titled MODULAR BATTERY POWERED HANDHELD SURGICAL INSTRUMENT WITH CURVED END EFFECTORS HAVING ASYMMETRIC ENGAGEMENT BETWEEN JAW AND BLADE, now U.S. Patent Application Publication No. 2017/0202609.
- (193) In the following detailed description, reference is made to the accompanying drawings, which form a part hereof. In the drawings, similar symbols and reference characters typically identify similar components throughout the several views, unless context dictates otherwise. The illustrative aspects described in the detailed description, drawings, and claims are not meant to be limiting. Other aspects may be utilized, and other changes may be made, without departing from the scope of the subject matter presented here.

(194) Before explaining the various aspects of the present disclosure in detail, it should be noted that the various aspects disclosed herein are not limited in their application or use to the details of construction and arrangement of parts illustrated in the accompanying drawings and description. Rather, the disclosed aspects may be positioned or incorporated in other aspects, variations and modifications thereof, and may be practiced or carried out in various ways. Accordingly, aspects disclosed herein are illustrative in nature and are not meant to limit the scope or application thereof. Furthermore, unless otherwise indicated, the terms and expressions employed herein have been chosen for the purpose of describing the aspects for the convenience of the reader and are not to limit the scope thereof. In addition, it should be understood that any one or more of the disclosed aspects, expressions of aspects, and/or examples thereof, can be combined with any one or more of the other disclosed aspects, expressions of aspects, and/or examples thereof, without limitation.

(195) Also, in the following description, it is to be understood that terms such as front, back, inside, outside, top, bottom and the like are words of convenience and are not to be construed as limiting terms. Terminology used herein is not meant to be limiting insofar as devices described herein, or portions thereof, may be attached or utilized in other orientations. The various aspects will be described in more detail with reference to the drawings.

(196) In various aspects, the present disclosure is directed to a mixed energy surgical instrument that utilizes both ultrasonic and RF energy modalities. The mixed energy surgical instrument may use modular shafts using that accomplish existing end-effector functions such as ultrasonic functions disclosed in U.S. Pat. No. 9,107,690, which is incorporated herein by reference in its entirety, combination device functions disclosed in U.S. Pat. Nos. 8,696,666 and 8,663,223, which are both incorporated herein by reference in their entireties, RF opposed electrode functions disclosed in U.S. Pat. Nos. 9,028,478 and 9,113,907, which are both incorporated herein by reference in their entireties, and RF I-blade offset electrode functions as disclosed in U.S. Patent Application Publication No. 2013/0023868, now U.S. Pat. No. 9,545,253, which is incorporated herein by reference in its entirety.

(197) In various aspects, the present disclosure is directed to a modular battery powered handheld ultrasonic surgical instrument comprising a first generator, a second generator, and a control circuit for controlling the energy modality applied by the surgical instrument. The surgical instrument is configured to apply at least one energy modality that comprises an ultrasonic energy modality, a radio frequency (RF) energy modality, or a combination ultrasonic and RF energy modalities.

(198) In another aspect, the present disclosure is directed to a modular battery powered handheld surgical instrument that can be configured for ultrasonic energy modality, RF modality, or a combination of ultrasonic and RF energy modalities. A mixed energy surgical instrument utilizes both ultrasonic and RF energy modalities. The mixed energy surgical instrument may use modular shafts that accomplish end effector functions. The energy modality may be selectable based on a measure of specific measured tissue and device parameters, such as, for example, electrical impedance, tissue impedance, electric motor current, jaw gap, tissue thickness, tissue compression, tissue type, temperature, among other parameters, or a combination thereof, to determine a suitable energy modality algorithm to employ ultrasonic vibration and/or electrosurgical high-frequency current to carry out surgical coagulation/cutting treatments on the living tissue based on the measured tissue parameters identified by the surgical instrument. Once the tissue parameters have been identified, the surgical instrument may be configured to control treatment energy applied to the tissue in a single or segmented RF electrode configuration or in an ultrasonic device, through the measurement of specific tissue/device parameters. Tissue treatment algorithms are described in commonly owned U.S. patent application Ser. No. 15/177,430, titled SURGICAL INSTRUMENT WITH USER ADAPTABLE TECHNIQUES, now U.S. Patent Application Publication No. 2017/0000541, which is herein incorporated by reference in its entirety.

(199) In another aspect, the present disclosure is directed to a modular battery powered handheld surgical instrument having a motor and a controller, where a first limiting threshold is used on the

motor for the purpose of attaching a modular assembly and a second threshold is used on the motor and is associated with a second assembly step or functionality of the surgical instrument. The surgical instrument may comprise a motor driven actuation mechanism utilizing control of motor speed or torque through measurement of motor current or parameters related to motor current, wherein motor control is adjusted via a non-linear threshold to trigger motor adjustments at different magnitudes based on position, inertia, velocity, acceleration, or a combination thereof. Motor driven actuation of a moving mechanism and a motor controller may be employed to control the motor velocity or torque. A sensor associated with physical properties of the moving mechanism provides feedback to the motor controller. In one aspect, the sensor is employed to adjust a predefined threshold which triggers a change in the operation of the motor controller. A motor may be utilized to drive shaft functions such as shaft rotation and jaw closure and switching that motor to also provide a torque limited waveguide attachment to a transducer. A motor control algorithm may be utilized to generate tactile feedback to a user through a motor drive train for indication of device status and/or limits of the powered actuation. A motor powered modular advanced energy based surgical instrument may comprise a series of control programs or algorithms to operate a series of different shaft modules and transducers. In one aspect, the programs or algorithms reside in a module and are uploaded to a control handle when attached. The motor driven modular battery powered handheld surgical instrument may comprise a primary rotary drive capable of being selectably coupleable to at least two independent actuation functions (first, second, both, neither) and utilize a clutch mechanism located in a distal modular elongated tube.

(200) In another aspect, the present disclosure is directed to modular battery powered handheld surgical instrument comprising energy conservation circuits and techniques using sleep mode de-energizing of a segmented circuit with short cuts to minimize non-use power drain and differing wake-up sequence order than the order of a sleep sequence. A disposable primary cell battery pack may be utilized with a battery powered modular handheld surgical instrument. The disposable primary cell may comprise power management circuits to compensate the battery output voltage with additional voltage to offset voltage sags under load and to prevent the battery pack output voltage from sagging below a predetermined level during operation under load. The circuitry of the surgical instrument comprises radiation tolerant components and amplification of electrical signals may be divided into multiple stages. An ultrasonic transducer housing or RF housing may contain the final amplification stage and may comprise different ratios depending on an energy modality associated with the ultrasonic transducer or RF module.

(201) In another aspect, the present disclosure is directed to a modular battery powered handheld surgical instrument comprising multiple magnetic position sensors along a length of a shaft and paired in different configurations to allow multiple sensors to detect the same magnet in order to determine three dimensional position of actuation components of the shaft from a stationary reference plane and simultaneously diagnosing any error from external sources. Control and sensing electronics may be incorporated in the shaft. A portion of the shaft control electronics may be disposed along the inside of moving shaft components and are separated from other shaft control electronics that are disposed along the outside of the moving shaft components. Control and sensing electronics may be situated and designed such that they act as a shaft seal in the device.

(202) In another aspect, the present disclosure is directed to a modular battery powered handheld surgical instrument comprising self diagnosing control switches within a battery powered, modular, reusable handle. The control switches are capable of adjusting their thresholds for triggering an event as well as being able to indicate external influences on the controls or predict time till replacement needed. The reusable handle housing is configured for use with modular disposable shafts and at least one control and wiring harness. The handle is configured to asymmetrically part when opened so that the switches, wiring harness, and/or control electronics can be supportably housed in one side such that the other side is removably attached to cover the primary housing.

(203) FIG. 1 is a diagram of a modular battery powered handheld ultrasonic surgical instrument **100**, according to an aspect of the present disclosure. FIG. 2 is an exploded view of the surgical instrument **100** shown in FIG. 1, according to an aspect of the present disclosure. With reference now to FIGS. 1 and 2, the surgical instrument **100** comprises a handle assembly **102**, an ultrasonic transducer/generator assembly **104**, a battery assembly **106**, a shaft assembly **110**, and an end effector **112**. The ultrasonic transducer/generator assembly **104**, battery assembly **106**, and shaft assembly **110** are modular components that are removably connectable to the handle assembly **102**. The handle assembly **102** comprises a motor assembly **160**. In addition, some aspects of the surgical instrument **100** include battery assemblies **106** that contain the ultrasonic generator and motor control circuits. The battery assembly **106** includes a first stage generator function with a final stage existing as part of the ultrasonic transducer/generator assembly **104** for driving 55 kHz and 33.1 KHz ultrasonic transducers. A different final stage generator for interchangeable use with the battery assembly **106**, common generator components, and segmented circuits enable battery assembly **106** to power up sections of the drive circuits in a controlled manner and to enable checking of stages of the circuit before powering them up and enabling power management modes. In addition, general purpose controls may be provide in the handle assembly **102** with dedicated shaft assembly **110** controls located on the shafts that have those functions. For instance, an end effector **112** module may comprise distal rotation electronics, the shaft assembly **110** may comprise rotary shaft control along with articulation switches, and the handle assembly **102** may comprise energy activation controls and jaw member **114** trigger **108** controls to clamp and unclamp the end effector **112**.

(204) The ultrasonic transducer/generator assembly **104** comprises a housing **148**, a display **176**, such as a liquid crystal display (LCD), for example, an ultrasonic transducer **130**, and an ultrasonic generator **162** (FIG. 4). The shaft assembly **110** comprises an outer tube **144** an ultrasonic transmission waveguide **145**, and an inner tube (not shown). The end effector **112** comprises a jaw member **114** and an ultrasonic blade **116**. As described hereinbelow, a motor or other mechanism operated by the trigger **108** may be employed to close the jaw member **114**. The ultrasonic blade **116** is the distal end of the ultrasonic transmission waveguide **145**. The jaw member **114** is pivotally rotatable to grasp tissue between the jaw member and the ultrasonic blade **116**. The jaw member **114** is operably coupled to a trigger **108** such that when the trigger **108** is squeezed the jaw member **114** closes to grasp tissue and when the trigger **108** is released the jaw member **114** opens to release tissue. In a one-stage trigger configuration, the trigger **108** functions to close the jaw member **114** when the trigger **108** is squeezed and to open the jaw member **114** when the trigger **108** is released. Once the jaw member **114** is closed, the switch **120** is activated to energize the ultrasonic generator to seal and cut the tissue. In a two-stage trigger configuration, during the first stage, the trigger **108** is squeezed part of the way to close the jaw member **114** and, during the second stage, the trigger **108** is squeezed the rest of the way to energize the ultrasonic generator to seal and cut the tissue. The jaw member **114a** opens by releasing the trigger **108** to release the tissue. It will be appreciated that in other aspects, the ultrasonic transducer **103** may be activated without the jaw member **114** being closed.

(205) The battery assembly **106** is electrically connected to the handle assembly **102** by an electrical connector **132**. The handle assembly **102** is provided with a switch **120**. The ultrasonic blade **116** is activated by energizing the ultrasonic transducer/generator circuit by actuating the switch **120**. The battery assembly **106**, according to one aspect, is a rechargeable, reusable battery pack with regulated output. In some cases, as is explained below, the battery assembly **106** facilitates user-interface functions. The handle assembly **102** is a disposable unit that has bays or docks for attachment to the battery assembly **106**, the ultrasonic transducer/generator assembly **104**, and the shaft assembly **110**. The handle assembly **102** also houses various indicators including, for example, a speaker/buzzer and activation switches. In one aspect, the battery

assembly is a separate component that is inserted into the housing of the handle assembly through a door or other opening defined by the housing of the handle assembly.

(206) The ultrasonic transducer/generator assembly **104** is a reusable unit that produces high frequency mechanical motion at a distal output. The ultrasonic transducer/generator assembly **104** is mechanically coupled to the shaft assembly **110** and the ultrasonic blade **116** and, during operation of the device, produces movement at the distal output of the ultrasonic blade **116**. In one aspect, the ultrasonic transducer/generator assembly **104** also provides a visual user interface, such as, through a red/green/blue (RGB) light-emitting diode (LED), LCD, or other display. As such, a visual indicator of the battery status is uniquely not located on the battery and is, therefore, remote from the battery.

(207) In accordance with various aspects of the present disclosure, the three components of the surgical instrument **100**, e.g., the ultrasonic transducer/generator assembly **104**, the battery assembly **106**, and the shaft assembly **110**, are advantageously quickly disconnectable from one or more of the others. Each of the three components of the surgical instrument **100** is sterile and can be maintained wholly in a sterile field during use. Because the components of the surgical instrument **100** are separable, the surgical instrument **100** can be composed of one or more portions that are single-use items (e.g., disposable) and others that are multi-use items (e.g., sterilizable for use in multiple surgical procedures). Aspects of the components separate as part of the surgical instrument **100**. In accordance with an additional aspect of the present disclosure, the handle assembly **102**, battery assembly **106**, and shaft assembly **110** components is equivalent in overall weight; each of the handle assembly **102**, battery assembly **106**, and shaft assembly **110** components is balanced so that they weigh the same or substantially the same. The handle assembly **102** overhangs the operator's hand for support, allowing the user's hand to more freely operate the controls of the surgical instrument **100** without bearing the weight. This overhang is set to be very close to the center of gravity. This combined with a triangular assembly configuration, makes the surgical instrument **100** advantageously provided with a center of balance that provides a very natural and comfortable feel to the user operating the device. That is, when held in the hand of the user, the surgical instrument **100** does not have a tendency to tip forward or backward or side-to-side, but remains relatively and dynamically balanced so that the waveguide is held parallel to the ground with very little effort from the user. Of course, the instrument can be placed in non-parallel angles to the ground just as easily.

(208) A rotation knob **118** is operably coupled to the shaft assembly **110**. Rotation of the rotation knob **118** $\pm 360^\circ$ in the direction indicated by the arrows **126** causes an outer tube **144** to rotate $\pm 360^\circ$ in the respective direction of the arrows **128**. In one aspect, the rotation knob **118** may be configured to rotate the jaw member **114** while the ultrasonic blade **116** remains stationary and a separate shaft rotation knob may be provided to rotate the outer tube **144** $\pm 360^\circ$. In various aspects, the ultrasonic blade **116** does not have to stop at $\pm 360^\circ$ and can rotate at an angle of rotation that is greater than $\pm 360^\circ$. The outer tube **144** may have a diameter $D_{sub.1}$ ranging from 5 mm to 10 mm, for example.

(209) The ultrasonic blade **116** is coupled to an ultrasonic transducer **130** (FIG. 2) portion of the ultrasonic transducer/generator assembly **104** by an ultrasonic transmission waveguide located within the shaft assembly **110**. The ultrasonic blade **116** and the ultrasonic transmission waveguide may be formed as a unit construction from a material suitable for transmission of ultrasonic energy. Examples of such materials include Ti6Al4V (an alloy of Titanium including Aluminum and Vanadium), Aluminum, Stainless Steel, or other suitable materials. Alternately, the ultrasonic blade **116** may be separable (and of differing composition) from the ultrasonic transmission waveguide, and coupled by, for example, a stud, weld, glue, quick connect, or other suitable known methods. The length of the ultrasonic transmission waveguide may be an integral number of one-half wavelengths ($n\lambda/2$), for example. The ultrasonic transmission waveguide may be preferably fabricated from a solid core shaft constructed out of material suitable to propagate ultrasonic

energy efficiently, such as the titanium alloy discussed above (i.e., Ti6Al4V) or any suitable aluminum alloy, or other alloys, or other materials such as sapphire, for example.

(210) The ultrasonic transducer/generator assembly **104** also comprises electronic circuitry for driving the ultrasonic transducer **130**. The ultrasonic blade **116** may be operated at a suitable vibrational frequency range may be about 20 Hz to 120 KHz and a well-suited vibrational frequency range may be about 30-100 KHz. A suitable operational vibrational frequency may be approximately 55.5 kHz, for example. The ultrasonic transducer **130** is energized by the actuating the switch **120**.

(211) It will be appreciated that the terms “proximal” and “distal” are used herein with reference to a clinician gripping the handle assembly **102**. Thus, the ultrasonic blade **116** is distal with respect to the handle assembly **102**, which is more proximal. It will be further appreciated that, for convenience and clarity, spatial terms such as “top” and “bottom” also are used herein with respect to the clinician gripping the handle assembly **102**. However, surgical instruments are used in many orientations and positions, and these terms are not intended to be limiting and absolute.

(212) FIG. 3 is an exploded view of a modular shaft assembly **110** of the surgical instrument **100** shown in FIG. 1, according to aspect of the present disclosure. The surgical instrument **100** uses ultrasonic vibration to carry out a surgical treatment on living tissue. The shaft assembly **110** couples to the handle assembly **102** via slots **142a**, **142b** formed on the handle assembly **102** and tabs **134a**, **134b** on the shaft assembly **110**. The handle assembly **102** comprises a male coupling member **136** that is received in a corresponding female coupling member in the **138** shaft assembly **110**. The male coupling member **136** is operably coupled to the trigger **108** such that when the trigger **108** is squeezed the male coupling member **136** translates distally to drive a closure tube mechanism **140** that translates an outer tube portion of the shaft assembly **110** to close the jaw member **114**. As previously discussed, when the trigger **108** is released, the jaw member **114** opens. The male coupling member **136** also couples to the ultrasonic transmission waveguide **145** (FIG. 2) located within the outer tube **144** of the shaft assembly **110** and couples to the ultrasonic transducer **130** (FIG. 2), which is received within the nozzle **146** of the handle assembly **102**. The shaft assembly **110** is electrically coupled to the handle assembly **102** via electrical contacts **137**.

(213) FIG. 4 is a perspective transparent view of the ultrasonic transducer/generator assembly **104** of the surgical instrument **100** shown in FIG. 1, according to aspect of the present disclosure. FIG. 5 is an end view of the ultrasonic transducer/generator assembly **104**, FIG. 6 is a perspective view of the ultrasonic transducer/generator assembly **104** with the top housing portion removed to expose the ultrasonic generator **162**, and FIG. 7 is a sectional view of the of the ultrasonic transducer/generator assembly **104**. With reference now to FIGS. 4-7, the ultrasonic transducer/generator assembly **104** comprises an ultrasonic transducer **130**, an ultrasonic generator **162** to drive the ultrasonic transducer **130**, and a housing **148**. A first electrical connector **158** couples the ultrasonic generator **162** to the battery assembly **106** (FIGS. 1 and 2) and a second electrical connector **161** couples the ultrasonic generator **162** to the nozzle (FIG. 3). In one aspect, a display **176** may be provided on one side of the ultrasonic transducer/generator assembly **104** housing **148**.

(214) The ultrasonic generator **162** comprises an ultrasonic driver circuit such as the electrical circuit **177** shown in FIG. 11 and, in some aspects, a second stage amplifier circuit **178**. The electrical circuit **177** is configured for driving the ultrasonic transducer **130** and forms a portion of the ultrasonic generator circuit. The electrical circuit **177** comprises a transformer **166** and a blocking capacitor **168**, among other components. The transformer **166** is electrically coupled to the piezoelectric elements **150a**, **150b**, **150c**, **150d** of the ultrasonic transducer **130**. The electrical circuit **177** is electrically coupled to first electrical connector **158** via a first cable **179**. The first electrical connector **158** is electrically coupled to the battery assembly **106** (FIGS. 1 and 2). The electrical circuit **177** is electrically coupled to second electrical connector **160** via a second cable **183**. The second electrical connector **160** is electrically coupled to the nozzle **146** (FIG. 3). In one

aspect, the second stage amplifier circuit **178** may be employed in a two stage amplification system.

(215) The ultrasonic transducer **130**, which is known as a “Langevin stack”, generally includes a transduction portion comprising piezoelectric elements **150a-150d**, a first resonator portion or end-bell **164**, and a second resonator portion or fore-bell **152**, and ancillary components. The total construction of these components is a resonator. There are other forms of transducers, such as magnetostrictive transducers, that could also be used. The ultrasonic transducer **130** is preferably an integral number of one-half system wavelengths ($n\lambda/2$; where “n” is any positive integer; e.g., $n=1, 2, 3 \dots$) in length as will be described in more detail later. An acoustic assembly includes the end-bell **164**, ultrasonic transducer **130**, fore-bell **152**, and a velocity transformer **154**.

(216) The distal end of the end-bell **164** is acoustically coupled to the proximal end of the piezoelectric element **150a**, and the proximal end of the fore-bell **152** is acoustically coupled to the distal end of the piezoelectric element **150d**. The fore-bell **152** and the end-bell **164** have a length determined by a number of variables, including the thickness of the transduction portion, the density and modulus of elasticity of the material used to manufacture the end-bell **164** and the fore-bell **152**, and the resonant frequency of the ultrasonic transducer **130**. The fore-bell **152** may be tapered inwardly from its proximal end to its distal end to amplify the ultrasonic vibration amplitude at the velocity transformer **154**, or alternately may have no amplification. A suitable vibrational frequency range may be about 20 Hz to 120 KHz and a well-suited vibrational frequency range may be about 30-100 KHz. A suitable operational vibrational frequency may be approximately 55.5 kHz, for example.

(217) The ultrasonic transducer **130** comprises several piezoelectric elements **150a-150d** acoustically coupled or stacked to form the transduction portion. The piezoelectric elements **150a-150d** may be fabricated from any suitable material, such as, for example, lead zirconate-titanate, lead meta-niobate, lead titanate, barium titanate, or other piezoelectric ceramic material. Electrically conductive elements **170a, 170b, 170c, 170d** are inserted between the piezoelectric elements **150a-150d** to electrically couple the electrical circuit **177** to the piezoelectric elements **150a-150d**. The electrically conductive element **170a** located between piezoelectric elements **150a, 150b** and the electrically conductive element **170d** located between piezoelectric element **150d** and the fore-bell **152** are electrically coupled to the positive electrode **174a** of the electrical circuit **177**. The electrically conductive element **170b** located between piezoelectric elements **150b, 150c** and the electrically conductive element **170c** located between piezoelectric elements **150c, 150d** are electrically coupled to the negative electrode **174b** of the electrical circuit **177**. The positive and negative electrodes **174a, 174b** are electrically coupled to the electrical circuit **177** by electrical conductors.

(218) The ultrasonic transducer **130** converts the electrical drive signal from the electrical circuit **177** into mechanical energy that results in primarily a standing acoustic wave of longitudinal vibratory motion of the ultrasonic transducer **130** and the ultrasonic blade **116** (FIGS. **1** and **3**) at ultrasonic frequencies. In another aspect, the vibratory motion of the ultrasonic transducer **130** may act in a different direction. For example, the vibratory motion may comprise a local longitudinal component of a more complicated motion of the ultrasonic blade **116**. When the acoustic assembly is energized, a vibratory motion in the form of a standing wave is generated through the ultrasonic transducer **130** to the ultrasonic blade **116** at a resonance and amplitude determined by various electrical and geometrical parameters. The amplitude of the vibratory motion at any point along the acoustic assembly depends upon the location along the acoustic assembly at which the vibratory motion is measured. A minimum or zero crossing in the vibratory motion standing wave is generally referred to as a node (i.e., where motion is minimal), and a local absolute value maximum or peak in the standing wave is generally referred to as an anti-node (i.e., where local motion is maximal). The distance between an anti-node and its nearest node is one-quarter wavelength ($\lambda/4$).

(219) The wires transmit an electrical drive signal from the electrical circuit **177** to the positive

electrode **170a** and the negative electrode **170b**. The piezoelectric elements **150a-150d** are energized by the electrical signal supplied from the electrical circuit **177** in response to an actuator, such as the switch **120**, for example, to produce an acoustic standing wave in the acoustic assembly. The electrical signal causes disturbances in the piezoelectric elements **150a-150d** in the form of repeated small displacements resulting in large alternating compression and tension forces within the material. The repeated small displacements cause the piezoelectric elements **150a-150d** to expand and contract in a continuous manner along the axis of the voltage gradient, producing longitudinal waves of ultrasonic energy. The ultrasonic energy is transmitted through the acoustic assembly to the ultrasonic blade **116** (FIGS. **1** and **3**) via a transmission component or an ultrasonic transmission waveguide through the shaft assembly **110** (FIGS. **1-3**).

(220) In order for the acoustic assembly to deliver energy to the ultrasonic blade **116** (FIGS. **1** and **3**), components of the acoustic assembly are acoustically coupled to the ultrasonic blade **116**. A coupling stud **156** of the ultrasonic transducer **130** is acoustically coupled to the ultrasonic transmission waveguide **145** by a threaded connection such as a stud. In one aspect, the ultrasonic transducer **130** may be acoustically coupled to the ultrasonic transmission waveguide **145** as shown in FIGS. **10A** and **10B**.

(221) The components of the acoustic assembly are preferably acoustically tuned such that the length of any assembly is an integral number of one-half wavelengths ($n\lambda/2$), where the wavelength λ is the wavelength of a pre-selected or operating longitudinal vibration drive frequency f_a of the acoustic assembly. It is also contemplated that the acoustic assembly may incorporate any suitable arrangement of acoustic elements.

(222) The ultrasonic blade **116** (FIGS. **1** and **3**) may have a length that is an integral multiple of one-half system wavelengths ($n\lambda/2$). A distal end of the ultrasonic blade **116** may be disposed near an antinode in order to provide the maximum longitudinal excursion of the distal end. When the ultrasonic transducer **130** is energized, the distal end of the ultrasonic blade **116** may be configured to move in the range of, for example, approximately 10 to 500 microns peak-to-peak, and preferably in the range of about 30 to 150 microns, and in some aspects closer to 100 microns, at a predetermined vibrational frequency of 55 kHz, for example.

(223) FIG. **8** is an elevation view of an ultrasonic transducer/generator assembly **104** that is configured to operate at 31 kHz resonant frequency, according to one aspect of the present disclosure. FIG. **9** is an elevation view of an ultrasonic transducer/generator assembly **104'** that is configured to operate at 55 kHz resonant frequency, according to one aspect of the present disclosure. As can be seen, the ultrasonic transducer/generator assemblies **104**, **104'**, the housings **148** are the same size in order to fit into the nozzle **146** of the surgical instrument **100** shown in FIG. **3**. Nevertheless, the individual ultrasonic transducers **130**, **130'** will vary in size depending on the desired resonant frequency. For example, the ultrasonic transducer **130** shown in FIG. **8** is tuned at a resonant frequency of 31 kHz is physically larger than the ultrasonic transducer **130'** shown in FIG. **9**, which is tuned at a resonant frequency of 55 KHz. The coupling stud **156**, **156'** of the ultrasonic transducer **130**, **130'** may be acoustically coupled to the ultrasonic transmission waveguide **145** by a threaded connection such as a stud.

(224) FIGS. **10A** and **10B** illustrate a shifting assembly **200** that selectively rotates the ultrasonic transmission waveguide **145** with respect to the ultrasonic transducer **130** and urges them towards one another, according to one aspect of the present disclosure. FIG. **10A** illustrates the shifting assembly **200** with the ultrasonic transmission waveguide **145** and the ultrasonic transducer **130** in a disengaged configuration and FIG. **10B** illustrates the shifting assembly **200** with the ultrasonic transmission waveguide **145** and the ultrasonic transducer **130** in an engaged configuration. With reference now to both FIGS. **10A** and **10B**, the shifting assembly **200** is located in the handle assembly **102** of the surgical instrument **100**. One or more sleeves **204** hold the ultrasonic transducer **130** in place within the housing **148**. The distal end of the ultrasonic transducer **130** includes threads **202** that are engaged by a worm gear **206**. As the worm gear **206** rotates the

ultrasonic transducer **130** is urged in the direction indicated by the arrow **208** to thread the threaded coupling stud **156** into a threaded end of the ultrasonic transmission waveguide **145**. The worm gear **206** may be driven by a motor located within the handle assembly **102** of the surgical instrument **100**.

(225) In one aspect, the shifting assembly **200** may include a torque limited motor driven attachment of the ultrasonic transmission waveguide **145** via the motor located in the handle assembly **102** that controls shaft actuation of clamping, rotation, and articulation. The shifting assembly **200** in the handle assembly **102** applies the proper torque onto the ultrasonic transmission waveguide **145** into place with a predetermined minimum torque. For instance, the handle assembly **102** may include a transducer torqueing mechanism which shifts the primary motor longitudinally uncoupling the primary drive shaft spur gear and coupling the transducer torqueing gear which rotates the shaft and nozzle therefore screwing the wave guide into the transducer.

(226) FIG. **11** is a schematic diagram of one aspect of a electrical circuit **177** shown in FIG. **4**, suitable for driving an ultrasonic transducer **130**, according to one aspect of the present disclosure. The electrical circuit **177** comprises an analog multiplexer **180**. The analog multiplexer **180** multiplexes various signals from the upstream channels SCL-A/SDA-A such as ultrasonic, battery, and power control circuit. A current sensor **182** is coupled in series with the return or ground leg of the power supply circuit to measure the current supplied by the power supply. A field effect transistor (FET) temperature sensor **184** provides the ambient temperature. A pulse width modulation (PWM) watchdog timer **188** automatically generates a system reset if the main program neglects to periodically service it. It is provided to automatically reset the electrical circuit **177** when it hangs or freezes because of a software or hardware fault. It will be appreciated that the electrical circuit **177** may be configured as an RF driver circuit for driving the ultrasonic transducer **130** or for driving RF electrodes such as the electrical circuit **702** shown in FIG. **34**, for example. Accordingly, with reference now back to FIG. **11**, the electrical circuit **177** can be used to drive both ultrasonic transducers and RF electrodes interchangeably. If driven simultaneously, filter circuits may be provided in the corresponding first stage circuits **5504** to select either the ultrasonic waveform or the RF waveform. Such filtering techniques are described in commonly owned U.S. patent application Ser. No. 15/265,293, titled TECHNIQUES FOR CIRCUIT TOPOLOGIES FOR COMBINED GENERATOR, now U.S. Pat. No. 10,610,286, which is herein incorporated by reference in its entirety.

(227) A drive circuit **186** provides left and right ultrasonic energy outputs. A digital signal the represents the signal waveform is provided to the SCL-A/SDA-A inputs of the analog multiplexer **180** from a control circuit, such as the control circuit **210** (FIG. **14**). A digital-to-analog converter **190** (DAC) converts the digital input to an analog output to drive a PWM circuit **192** coupled to an oscillator **194**. The PWM circuit **192** provides a first signal to a first gate drive circuit **196a** coupled to a first transistor output stage **198a** to drive a first ultrasonic (Left) energy output. The PWM circuit **192** also provides a second signal to a second gate drive circuit **196b** coupled to a second transistor output stage **198b** to drive a second ultrasonic (Right) energy output. A voltage sensor **199** is coupled between the Ultrasonic Left/Right output terminals to measure the output voltage. The drive circuit **186**, the first and second drive circuits **196a**, **196b**, and the first and second transistor output stages **198a**, **198b** define a first stage amplifier circuit. In operation, the control circuit **210** (FIG. **14**) generates a digital waveform **1800** (FIG. **67**) employing circuits such as direct digital synthesis (DDS) circuits **1500**, **1600** (FIGS. **65** and **66**). The DAC **190** receives the digital waveform **1800** and converts it into an analog waveform, which is received and amplified by the first stage amplifier circuit.

(228) FIG. **12** is a schematic diagram of the transformer **166** coupled to the electrical circuit **177** shown in FIG. **11**, according to one aspect of the present disclosure. The Ultrasonic Left/Right input terminals (primary winding) of the transformer **166** are electrically coupled to the Ultrasonic Left/Right output terminals of the electrical circuit **177**. The secondary winding of the transformer

166 are coupled to the positive and negative electrodes **174a**, **174b**. The positive and negative electrodes **174a**, **174b** of the transformer **166** are coupled to the positive terminal **170a** (Stack 1) and the negative terminal **170b** (Stack 2) of the ultrasonic transducer **130** (FIG. 4). In one aspect, the transformer **166** has a turns-ratio of $n_1:n_2$ of 1:50.

(229) FIG. 13 is a schematic diagram of the transformer **166** shown in FIG. 12 coupled to a test circuit **165**, according to one aspect of the present disclosure. The test circuit **165** is coupled to the positive and negative electrodes **174a**, **174b**. A switch **167** is placed in series with an inductor/capacitor/resistor (LCR) load that simulates the load of an ultrasonic transducer.

(230) FIG. 14 is a schematic diagram of a control circuit **210**, according to one aspect of the present disclosure. The control circuit **210** is located within a housing of the battery assembly **106**. The battery assembly **106** is the energy source for a variety of local power supplies **215**. The control circuit comprises a main processor **214** coupled via an interface master **218** to various downstream circuits by way of outputs SCL-A/SDA-A, SCL-B/SDA-B, SCL-C/SDA-C, for example. In one aspect, the interface master **218** is a general purpose serial interface such as an I²C serial interface. The main processor **214** also is configured to drive switches **224** through general purposes input output **220** (GPIO), a display **226** (e.g., and LCD display), and various indicators **228** through GPIO **222**. A watchdog processor **216** is provided to control the main processor **214**. A switch **230** is provided in series with the battery **211** to activate the control circuit **212** upon insertion of the battery assembly **106** into the handle assembly **102** (FIGS. 1-3).

(231) In one aspect, the main processor **214** is coupled to the electrical circuit **177** (FIGS. 4 and 11) by way of output terminals SCL-A/SDA-A. The main processor **214** comprises a memory for storing tables of digitized drive signals or waveforms that are transmitted to the electrical circuit **177** for driving the ultrasonic transducer **130** (FIGS. 4-8), for example. In other aspects, the main processor **214** may generate a digital waveform and transmit it to the electrical circuit **177** or may store the digital waveform for later transmission to the electrical circuit **177**. The main processor **214** also may provide RF drive by way of output terminals SCL-B/SDA-B and various sensors (e.g., Hall-effect sensors, magnetorheological fluid (MRF) sensors, etc.) by way of output terminals SCL-C/SDA-C. In one aspect, the main processor **214** is configured to sense the presence of ultrasonic drive circuitry and/or RF drive circuitry to enable appropriate software and user interface functionality.

(232) In one aspect, the main processor **214** may be an LM 4F230H5QR, available from Texas Instruments, for example. In at least one example, the Texas Instruments LM4F230H5QR is an ARM Cortex-M4F Processor Core comprising on-chip memory of 256 KB single-cycle flash memory, or other non-volatile memory, up to 40 MHz, a prefetch buffer to improve performance above 40 MHz, a 32 KB single-cycle serial random access memory (SRAM), internal read-only memory (ROM) loaded with StellarisWare® software, 2 KB electrically erasable programmable read-only memory (EEPROM), one or more pulse width modulation (PWM) modules, one or more quadrature encoder inputs (QED analog, one or more 12-bit Analog-to-Digital Converters (ADC) with 12 analog input channels, among other features that are readily available for the product datasheet. Other processors may be readily substituted and, accordingly, the present disclosure should not be limited in this context.

(233) FIG. 15 shows a simplified block circuit diagram illustrating another electrical circuit **300** contained within a modular ultrasonic surgical instrument **334**, according to one aspect of the present disclosure. The electrical circuit **300** includes a processor **302**, a clock **330**, a memory **326**, a power supply **304** (e.g., a battery), a switch **306**, such as a metal-oxide semiconductor field effect transistor (MOSFET) power switch, a drive circuit **308** (PLL), a transformer **310**, a signal smoothing circuit **312** (also referred to as a matching circuit and can be, e.g., a tank circuit), a sensing circuit **314**, a transducer **130**, and a shaft assembly **110** comprising an ultrasonic transmission waveguide that terminates at an ultrasonic blade **116**, which may be referred to herein simply as the waveguide.

(234) One feature of the present disclosure that severs dependency on high voltage (120 VAC) input power (a characteristic of general ultrasonic cutting devices) is the utilization of low-voltage switching throughout the wave-forming process and the amplification of the driving signal only directly before the transformer stage. For this reason, in one aspect of the present disclosure, power is derived from only a battery, or a group of batteries, small enough to fit either within the handle assembly **102** (FIGS. 1-3). State-of-the-art battery technology provides powerful batteries of a few centimeters in height and width and a few millimeters in depth. By combining the features of the present disclosure to provide a self-contained and self-powered ultrasonic device, a reduction in manufacturing cost may be achieved.

(235) The output of the power supply **304** is fed to and powers the processor **302**. The processor **302** receives and outputs signals and, as will be described below, functions according to custom logic or in accordance with computer programs that are executed by the processor **302**. The electrical circuit **300** can also include a memory **326**, preferably, random access memory (RAM), that stores computer-readable instructions and data.

(236) The output of the power supply **304** also is directed to a switch **306** having a duty cycle controlled by the processor **302**. By controlling the on-time for the switch **306**, the processor **302** is able to dictate the total amount of power that is ultimately delivered to the transducer **316**. In one aspect, the switch **306** is a MOSFET, although other switches and switching configurations are adaptable as well. The output of the switch **306** is fed to a drive circuit **308** that contains, for example, a phase detecting phase-locked loop (PLL) and/or a low-pass filter and/or a voltage-controlled oscillator. The output of the switch **306** is sampled by the processor **302** to determine the voltage and current of the output signal (V_{IN} and I_{IN} , respectively). These values are used in a feedback architecture to adjust the pulse width modulation of the switch **306**. For instance, the duty cycle of the switch **306** can vary from about 20% to about 80%, depending on the desired and actual output from the switch **306**.

(237) The drive circuit **308**, which receives the signal from the switch **306**, includes an oscillatory circuit that turns the output of the switch **306** into an electrical signal having an ultrasonic frequency, e.g., 55 kHz (VCO). As explained above, a smoothed-out version of this ultrasonic waveform is ultimately fed to the ultrasonic transducer **130** to produce a resonant sine wave along the ultrasonic transmission waveguide **145** (FIG. 2).

(238) At the output of the drive circuit **308** is a transformer **310** that is able to step up the low voltage signal(s) to a higher voltage. It is noted that upstream switching, prior to the transformer **310**, is performed at low (e.g., battery driven) voltages, something that, to date, has not been possible for ultrasonic cutting and cautery devices. This is at least partially due to the fact that the device advantageously uses low on-resistance MOSFET switching devices. Low on-resistance MOSFET switches are advantageous, as they produce lower switching losses and less heat than a traditional MOSFET device and allow higher current to pass through. Therefore, the switching stage (pre-transformer) can be characterized as low voltage/high current. To ensure the lower on-resistance of the amplifier MOSFET(s), the MOSFET(s) are run, for example, at 10 V. In such a case, a separate 10 VDC power supply can be used to feed the MOSFET gate, which ensures that the MOSFET is fully on and a reasonably low on resistance is achieved. In one aspect of the present disclosure, the transformer **310** steps up the battery voltage to 120V root-mean-square (RMS). Transformers are known in the art and are, therefore, not explained here in detail.

(239) In the circuit configurations described, circuit component degradation can negatively impact the circuit performance of the circuit. One factor that directly affects component performance is heat. Known circuits generally monitor switching temperatures (e.g., MOSFET temperatures). However, because of the technological advancements in MOSFET designs, and the corresponding reduction in size, MOSFET temperatures are no longer a valid indicator of circuit loads and heat. For this reason, according to one aspect of the present disclosure, a sensing circuit **314** senses the temperature of the transformer **310**. This temperature sensing is advantageous as the transformer

310 is run at or very close to its maximum temperature during use of the device. Additional temperature will cause the core material, e.g., the ferrite, to break down and permanent damage can occur. The present disclosure can respond to a maximum temperature of the transformer **310** by, for example, reducing the driving power in the transformer **310**, signaling the user, turning the power off, pulsing the power, or other appropriate responses.

(240) In one aspect of the present disclosure, the processor **302** is communicatively coupled to the end effector **112**, which is used to place material in physical contact with the ultrasonic blade **116**, e.g., the clamping mechanism shown in FIG. 1. Sensors are provided that measure, at the end effector **112**, a clamping force value (existing within a known range) and, based upon the received clamping force value, the processor **302** varies the motional voltage VM. Because high force values combined with a set motional rate can result in high blade temperatures, a temperature sensor **336** can be communicatively coupled to the processor **302**, where the processor **302** is operable to receive and interpret a signal indicating a current temperature of the blade from the temperature sensor **336** and to determine a target frequency of blade movement based upon the received temperature. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the trigger **108** to measure the force applied to the trigger **108** by the user. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the switch **120** button such that displacement intensity corresponds to the force applied by the user to the switch **120** button.

(241) According to one aspect of the present disclosure, the PLL portion of the drive circuit **308**, which is coupled to the processor **302**, is able to determine a frequency of waveguide movement and communicate that frequency to the processor **302**. The processor **302** stores this frequency value in the memory **326** when the device is turned off. By reading the clock **330**, the processor **302** is able to determine an elapsed time after the device is shut off and retrieve the last frequency of waveguide movement if the elapsed time is less than a predetermined value. The device can then start up at the last frequency, which, presumably, is the optimum frequency for the current load.

(242) FIG. 16 shows a battery assembly **400** for use with the surgical instrument **100**, according to one aspect of the present disclosure. The battery assembly **400** comprises a housing **402** sized and configured to contain various energy cells. The energy cells may include rechargeable and non-rechargeable batteries. In one aspect, the battery assembly **400** includes four Li-ion non-rechargeable batteries **404a**, **404b**, **404c**, **404d** and two nickel metal hydride (NiMH) rechargeable batteries **406a** (the second battery is not shown). The housing **402** comprises tabs **408a**, **408b** to removably connect the battery assembly **400** to the handle assembly **102** of the surgical instrument **100** (FIGS. 1 and 2).

(243) FIG. 17 shows a disposable battery assembly **410** for use with the surgical instrument **100**, according to one aspect of the present disclosure. In one aspect, the disposable battery assembly **410** comprises a primary cell battery pack for use with a battery powered advanced energy instrument such as the surgical instrument **100** (FIGS. 1 and 2), comprising compensating electronics with additional voltage to offset a voltage sag from the disposable battery assembly **410** to prevent the output voltage from sagging below a predetermined level during operation under load. The disposable battery assembly **410** comprises a housing **412** sized and configured to contain various energy cells. The energy cells may include rechargeable and non-rechargeable batteries. In one aspect, the disposable battery assembly **410** includes four primary Lithium-ion (Li-ion) non-rechargeable batteries **414a**, **414b**, **414c**, **414d** and two secondary NiMH or Nickel Cadmium (NiCd) rechargeable batteries **416a**, **416b**. The housing **412** comprises electrical contact **418** to electrically couple the disposable battery assembly **410** to the handle assembly **102** of the surgical instrument **100**. In the illustrated example the electrical contact **418** comprises four metal contacts. The disposable battery assembly **410** also includes electrical circuits **419** such as the control circuit **210** (FIG. 14) and/or the electrical circuit **300** (FIG. 15). The electrical circuits **419** are radiated hardened.

(244) In one aspect, the disposable battery assembly **410** includes batteries **414a-d**, electrical circuits **419**, and other componentry that is resistant to gamma or other radiation sterilization. For instance, a switching mode power supply **460** (FIG. 22) or a linear power supply **470** (FIG. 24) and an optional charge circuit may be incorporated within the housing **412** of the disposable battery assembly **410** to reduce voltage sag of the primary Li-ion batteries **414a-d** and to allow the secondary NiMH batteries **416a**, **416b** to be used to reduce voltage sag. This guarantees full charged cells at the beginning of each surgery that are easy to introduce into the sterile field. A dual type battery assembly including primary Li-ion batteries **414a-d** and secondary NiMH batteries **416a-b** can be used with dedicated energy cells **416a-b** to control the electronics from dedicated energy cells **414a-d** that run the generator and motor control circuits. In one aspect, the system pulls from the batteries involved in driving the electronics circuits in the case that batteries involved are dropping low. In one aspect, the system would include a one way diode system that would not allow for current to flow in the opposite direction, for example, from the batteries involved in driving the energy and/or motor control circuits to the batteries involved in driving the electronic circuits. In one additional aspect, the system may comprise a gamma friendly charge circuit and switch mode power supply using diodes and vacuum tube components that would minimize voltage sag at a predetermined level. The switch mode power supply may be eliminated by including a minimum sag voltage that is a division of the NiMH voltages (e.g., three NiMH cells). In another aspect, a modular system can be made wherein the radiation hardened components are located in a module, making this module sterilizable by radiation sterilization. Other non-radiation hardened components are included in other modular components and connections are made between the modular components such that the componentry operate together as if the components were located together on the same circuit board. If only two cells of the secondary NiMH batteries **416a-b** are desired the switch mode power supply based on diodes and vacuum tubes allows for sterilizable electronics within the disposable primary Li-ion batteries **414a-d**.

(245) FIG. 18 shows a reusable battery assembly **420** for use with the surgical instrument **100**, according to one aspect of the present disclosure. The reusable battery assembly **420** comprises a housing **422** sized and configured to contain various rechargeable energy cells. The energy cells may include rechargeable batteries. In one aspect, the reusable battery assembly **420** includes five laminated NiMH rechargeable batteries **424a**, **424b**, **424c**, **424d**, **424e**. The housing **422** comprises electrical contact **428** to electrically couple the reusable battery assembly **420** to the handle assembly **102** of the surgical instrument **100** (FIGS. 1 and 2). In the illustrated example, the electrical contact **428** comprises six metal contacts. The reusable battery assembly **420** also includes up to six circuit boards **429a**, **429b**, **429c**, **429d**, **429e**, **429f** that may include electrical circuits such as the control circuit **210** (FIG. 14) and/or the electrical circuit **300** (FIG. 15). In one aspect, the reusable battery assembly **420** comprises drive FET transistors and associated circuitry **429a-f** in the housing **422** for easy swap and no need to shut down the surgical instrument **100** (FIGS. 1 and 2) to replace the reusable battery assembly **420** with energy delivery.

(246) The reusable battery assembly **420** comprises a battery test switch **426** and up to three LED indicators **427a**, **427b**, **427c** to determine the health of the batteries **424a-e** in the reusable battery assembly **420**. The first LED indicator **427a** may indicate fully charged batteries **424a-e** that is ready to use. The second LED indicator **427b** may indicate that the battery needs to be recharged. The third LED indicator **427c** may indicate that battery is not good and to dispose. The reusable battery assembly **420** health indication to allow the user to determine the specific health and capabilities of the batteries **424a-e** before it is inserted and used. For instance, charge status of the rechargeable secondary cells, sag voltage, primary cell voltage are checked by the activation of the battery test switch **426** which could measure these in an unload state or with a predefined resistive load placed on the system. The voltages could have at least one but more preferably three thresholds to compare the resulting voltages checks to. In the case of the first indicator **427a**, the

batteries **424a-e** indicating whether or not they are suitable to use. With three levels the reusable battery assembly **420** could display full charge, minimum charge, and some marginal but limited charge status. This battery **424a-e** health monitor would be useful for either the disposable battery assembly **410** (FIG. **17**) or the reusable battery assembly **420**. In the case of the disposable battery assembly **410** it is a ready/damaged indicator. In the case of the reusable battery assembly **420** it could indicate life remaining, recharge capacity, even age before failure in addition to ready/not ready.

(247) FIG. **19** is an elevated perspective view of a removable battery assembly **430** with both halves of the housing shell removed exposing battery cells coupled to multiple circuit boards which are coupled to the multi-lead battery terminal in accordance with an aspect of the present disclosure. Further, more than or less than three circuit boards is possible to provide expanded or limited functionality. As shown in FIG. **19**, the multiple circuit boards **432**, **434**, **436** may be positioned in a stacked architecture, which provides a number of advantages. For example, due to the smaller layout size, the circuit boards have a reduced footprint within the removable battery assembly **430**, thereby allowing for a smaller battery. In addition, in this configuration, is possible to easily isolate power boards from digital boards to prevent any noise originating from the power boards to cause harm to the digital boards. Also, the stacked configuration allows for direct connect features between the boards, thereby reducing the presence of wires. Furthermore, the circuit boards can be configured as part of a rigid-flex-rigid circuit to allow the rigid parts to be “fanned” into a smaller volumetric area.

(248) According to aspects of the present disclosure, the circuit board **432**, **434**, **436** provides a specific function. For instance, one circuit board **432** can provide the components for carrying out the battery protection circuitry. Similarly, another circuit board **434** can provide the components for carrying out the battery controller. Another circuit board **436** can, for example, provide high power buck controller components. Finally, the battery protection circuitry can provide connection paths for coupling the battery cells **438a-n**. By placing the circuit boards in a stacked configuration and separating the boards by their respective functions, the boards may be strategically placed in a specific order that best handles their individual noise and heat generation. For example, the circuit board having the high-power buck controller components produces the most heat and, therefore, it can be isolated from the other boards and placed in the center of the stack. In this way, the heat can be kept away from the outer surface of the device in an effort to prevent the heat from being felt by the physician or operator of the device. In addition, the battery board grounds may be configured in a star topology with the center located at the buck controller board to reduce the noise created by ground loops.

(249) The strategically stacked circuit boards, the low thermal conductivity path from the circuit boards to the multi-lead battery terminal assembly, and a flex circuit **3516** are features that assist in preventing heat from reaching the exterior surface of the device. The battery cells and buck components are thermally connected to a flex circuit within the handle assembly **102** (FIGS. **1** and **2**) so that the heat generated by the cells and buck components enter a portion away from the physician's hand. The flex circuit presents a relatively high thermal mass, due to its broad area of exposure and the advantageous conduction characteristics of the copper, which redirects, absorbs, and/or dissipates heat across a broader area thereby slowing the concentration of heat and limiting high spot temperatures on the exterior surface of the device. Other techniques may be implemented as well, including, but not limited to, larger heat wells, sinks or insulators, a metal connector cap and heavier copper content in the flex circuit or the handle assembly **102** of the device.

(250) Another advantage of the removable battery assembly **430** is realized when Li-ion batteries are used. As previously stated, Li-ion batteries should not be charged in a parallel configuration of multiple cells. This is because, as the voltage increases in a particular cell, it begins to accept additional charge faster than the other lower-voltage cells. Therefore, the cells are monitored so that a charge to that cell can be controlled individually. When a Li-ion battery is formed from a group of

cells **438a-n**, a multitude of wires extending from the exterior of the device to the batteries **438a-n** is needed (at least one additional wire for each battery cell beyond the first). By having a removable battery assembly **430**, a battery cell **438a-n** can, in one aspect, have its own exposed set of contacts and, when the removable battery assembly **430** is not present inside the handle assembly **102** (FIGS. **1** and **2**), a set of contacts can be coupled to a corresponding set of contacts in an external, non-sterile, battery-charging device. In another aspect, a battery cell **438a-n** can be electrically connected to the battery protection circuitry to allow the battery protection circuitry to control and regulate recharging of a cell **438a-n**. The removable battery assembly **430** is provided with circuitry to prevent use of the removable battery assembly **430** past an expected term-of-life. This term is not only dictated by the cells but is also dictated by the outer surfaces, including the battery casing or shell and the upper contact assembly. Such circuitry will be explained in further detail below and includes, for example, a use count, a recharge count, and an absolute time from manufacture count.

(251) FIG. **19** also shows a multi-lead battery terminal assembly **433**, which is an interface that electrically couples the components within the removable battery assembly **430** to an electrical interface of the handle assembly **102** (FIGS. **1** and **2**). It is through the handle assembly **102** that the removable battery assembly **430** is able to electrically (and mechanically) couple with the ultrasonic transducer/generator assembly **104** (FIG. **4**). As is explained above, the removable battery assembly **430**, through the multi-lead battery terminal assembly **433**, provides power to the surgical instrument **100** (FIGS. **1** and **2**), as well as other functionality described herein. The multi-lead battery terminal assembly **433** includes a plurality of contacts pads **435a-n** capable of separately electrically connecting a terminal within the removable battery assembly **430** to another terminal provided by a docking bay of the handle assembly **102**. One example of such electrical connections coupled to the plurality of contact pads **435a-n** as power and communication signal paths. In the aspect of the multi-lead battery terminal assembly **433**, sixteen different contact pads **435a-n** are shown. This number is merely illustrative. In an aspect, an interior side of the battery terminal assembly **433** has a well formed on the molded terminal holder that can be filled with potting materials to create a gas tight seal. The contact pads **435a-n** are overmolded in the lid and extend through the potting well into the interior of the battery **430**. Here a flex circuit can be used to rearrange the array of pins and provide an electrical connection to the circuit boards. In one example, a 4×4 array is converted to a 2×8 array. In one example the multi-lead battery terminal assembly **433**, a plurality of contact pads **435a-n** of the multi-lead battery terminal assembly **2804** include a corresponding plurality of interior contact pins **437a-n**. A contact pin **437a** provides a direct electrical coupling to a corresponding one of the contact pads **435a**.

(252) FIG. **20** illustrates a battery test circuit **440**, according to one aspect of the present disclosure. The battery test circuit **440** includes the battery test switch **426** as described in FIG. **18**. The battery test switch **426** is a switch that engages an LCR dummy load that simulates a transducer or shaft assembly electronics. As described in FIG. **18**, additional indicator circuits may be coupled to the battery test circuit **440** to provide a suitable indication of the capacity of the batteries in the reusable battery assembly **420**. The illustrated battery test circuit **440** may be employed in any of the battery assemblies **400**, **410**, **420**, **430** described in connection with FIGS. **16-19**, respectively.

(253) FIG. **21** illustrates a supplemental power source circuit **450** to maintain a minimum output voltage, according to one aspect of the present disclosure. The supplemental power source circuit **450** may be included in any of the battery assemblies **400**, **410**, **420**, **430** described in connection with FIGS. **16-19**. The supplemental power source circuit **450** prevents the output voltage $V_{sub.o}$ from sagging under high load conditions. The supplemental power source circuit **450** includes a set of four primary batteries **452a-b**, **452c-d** (up to n batteries may be used) that are activated when the switch **453** closes upon insertion of the battery assembly **400**, **410**, **420**, **430** into the handle assembly **102** of the surgical instrument **100** (FIGS. **1** and **2**). The primary batteries **452a-d** may be Li-ion batteries such as CR123A Li-ion batteries. Under load, the primary batteries **452a-d** provide

the output voltage $V_{sub.o}$ while the secondary rechargeable battery **454** is charged by the battery charger **455**. In one aspect, the secondary rechargeable battery **454** in a NiMH battery and the battery charger **455** is a suitable NiMH charger. When the output voltage $V_{sub.o}$ sags or droops due to high load conditions the voltage $V_{sub.x}$ operates the switch mode power supply **456** to restore the output voltage $V_{sub.o}$ by supplying the additional current into the load. The diode **458** is provided to prevent current from flowing into the output of the switch mode power supply **456**. Accordingly, the output voltage $V_{sub.o}$ of the switch mode power supply **456** must exceed the voltage drop across the diode **458** ($\sim 0.7V$) before the supplemental current can flow into the load. Optionally, a battery test switch **459** and test resistor $R_{sub.Test}$ may be provided to test the supplemental power source circuit **450** under load conditions. In particular, in view of FIG. **21**, the battery assemblies **400**, **410**, **420**, **430** may comprise a test circuit **457a** comprising a switch **457b** and a resistor **457c** such that when the switch **457b** is closed (e.g., via the test button **426**), the resistor **457c** tests whether the primary batteries **452a-d** are capable of delivering the output voltage $V_{sub.o}$. Otherwise, the resistor **457** tests whether the secondary battery **454**, via operation of the switch mode power supply **456**, is capable of delivering a $V_{sub.b}$ such that supplemental current passing through the diode **458** restores the output voltage $V_{sub.o}$.

(254) FIG. **22** illustrates a switch mode power supply circuit **460** for supplying energy to the surgical instrument **100**, according to one aspect of the present disclosure. The switch mode power supply circuit **460** may be disposed within any one of the battery assemblies **400**, **410**, **430** described in connection with FIGS. **16**, **17**, and **19**, respectively. In the illustrated example, the switch mode power supply circuit **460** comprises primary Li cell batteries **429a-d** where the positive (+) output voltage is coupled to an input terminal $V_{sub.IN}$ of a switching regulator **464**. It will be appreciated that any suitable number of primary cells may be employed. The switch mode power supply circuit **460** includes a remote ON/OFF switch. The input $V_{sub.IN}$ of the switching regulator **464** also includes an input filter represented by capacitor $C_{sub.i}$. The output $V_{sub.OUT}$ of the switching regulator **464** is coupled to an inductor L and an output filter represented by capacitor $C_{sub.o}$. A catch diode D is disposed between $V_{sub.OUT}$ and ground. A feedback signal is provided from the output filter $C_{sub.o}$ to the FB input of the switching regulator **464**. A load resistor $R_{sub.L}$ represents a load. In one aspect, the minimum load is about 200 mA. In one aspect, the output voltage $V_{sub.OUT}$ is 3.3 VDC at 800 mA.

(255) FIG. **23** illustrates a discrete version of the switching regulator **464** shown in FIG. **22** for supplying energy to the surgical instrument **100**, according to one aspect of the present disclosure. The switching regulator **464** receives the input voltage from a battery assembly **400**, **410**, **420**, **430** at the $V_{sub.IN}$ terminal. The signal at the ON/OFF input enables or disables the operation of the switching regulator **464** by controlling the state of the switch **471**. A feedback signal is received from the load at the FB input where is divided by a voltage divider circuit **463**. The voltage from the voltage divider **463** is applied to the positive input of a fixed gain amplifier **465**. The negative input of the fixed gain amplifier **465** is coupled to a bandgap reference diode **469** (e.g., 1.23V). The amplified output of the fixed gain amplifier **465** is applied to the positive input of a comparator **466**. The negative input of the comparator **466** receives a 50 KHz oscillator **467** input. The output of the comparator **466** is applied to a driver **468** which drives and output transistor **461**. The output transistor **461** supplies voltage and current to the load via the $V_{sub.OUT}$ terminal.

(256) FIG. **24** illustrates a linear power supply circuit **470** for supplying energy to the surgical instrument **100**, according to one aspect of the present disclosure. The linear power supply circuit **470** may be disposed within any one of the battery assemblies **400**, **410**, **420**, **430** described in connection with FIGS. **16**, **17**, **18**, and **19**, respectively. In the illustrated example, the linear power supply circuit **470** comprises primary Li-ion cell batteries **462a-d** where the positive (+) output voltage is coupled to the $V_{sub.IN}$ terminal of transistor **472**. The output of the transistor **472** supplies the current and voltage to the load via the $V_{sub.OUT}$ terminal of the linear power supply circuit **470**. An input filter $C_{sub.i}$ is provided at the input side and an output filter $C_{sub.o}$ is

provided at an output side. A Zener diode D.sub.Z applies a regulated voltage to the base of the transistor **472**. A bias resistor biases the Zener diode D.sub.Z and the transistor **472**.

(257) FIG. **25** is an elevational exploded view of modular handheld ultrasonic surgical instrument **480** showing the left shell half removed from a handle assembly **482** exposing a device identifier communicatively coupled to the multi-lead handle terminal assembly in accordance with one aspect of the present disclosure. In additional aspects of the present disclosure, an intelligent or smart battery is used to power the modular handheld ultrasonic surgical instrument **480**. However, the smart battery is not limited to the modular handheld ultrasonic surgical instrument **480** and, as will be explained, can be used in a variety of devices, which may or may not have power requirements (e.g., current and voltage) that vary from one another. The smart battery assembly **486**, in accordance with one aspect of the present disclosure, is advantageously able to identify the particular device to which it is electrically coupled. It does this through encrypted or unencrypted identification methods. For instance, a smart battery assembly **486** can have a connection portion, such as connection portion **488**. The handle assembly **482** can also be provided with a device identifier communicatively coupled to the multi-lead handle terminal assembly **491** and operable to communicate at least one piece of information about the handle assembly **482**. This information can pertain to the number of times the handle assembly **482** has been used, the number of times an ultrasonic transducer/generator assembly **484** (presently disconnected from the handle assembly **482**) has been used, the number of times a waveguide shaft assembly **490** (presently connected to the handle assembly **482**) has been used, the type of the waveguide shaft assembly **490** that is presently connected to the handle assembly **482**, the type or identity of the ultrasonic transducer/generator assembly **484** that is presently connected to the handle assembly **482**, and/or many other characteristics. When the smart battery assembly **486** is inserted in the handle assembly **482**, the connection portion **488** within the smart battery assembly **486** makes communicating contact with the device identifier of the handle assembly **482**. The handle assembly **482**, through hardware, software, or a combination thereof, is able to transmit information to the smart battery assembly **486** (whether by self-initiation or in response to a request from the smart battery assembly **486**). This communicated identifier is received by the connection portion **488** of the smart battery assembly **486**. In one aspect, once the smart battery assembly **486** receives the information, the communication portion is operable to control the output of the smart battery assembly **486** to comply with the device's specific power requirements.

(258) In one aspect, the communication portion includes a processor **493** and a memory **497**, which may be separate or a single component. The processor **493**, in combination with the memory, is able to provide intelligent power management for the modular handheld ultrasonic surgical instrument **480**. This aspect is particularly advantageous because an ultrasonic device, such as the modular handheld ultrasonic surgical instrument **480**, has a power requirement (frequency, current, and voltage) that may be unique to the modular handheld ultrasonic surgical instrument **480**. In fact, the modular handheld ultrasonic surgical instrument **480** may have a particular power requirement or limitation for one dimension or type of outer tube **494** and a second different power requirement for a second type of waveguide having a different dimension, shape, and/or configuration.

(259) A smart battery assembly **486**, according to one aspect of the present disclosure, therefore, allows a battery assembly to be used amongst several surgical instruments. Because the smart battery assembly **486** is able to identify to which device it is attached and is able to alter its output accordingly, the operators of various different surgical instruments utilizing the smart battery assembly **486** no longer need be concerned about which power source they are attempting to install within the electronic device being used. This is particularly advantageous in an operating environment where a battery assembly needs to be replaced or interchanged with another surgical instrument in the middle of a complex surgical procedure.

(260) In a further aspect of the present disclosure, the smart battery assembly **486** stores in a

memory 497 a record of each time a particular device is used. This record can be useful for assessing the end of a device's useful or permitted life. For instance, once a device is used 20 times, such batteries in the smart battery assembly 486 connected to the device will refuse to supply power thereto—because the device is defined as a “no longer reliable” surgical instrument. Reliability is determined based on a number of factors. One factor can be wear, which can be estimated in a number of ways including the number of times the device has been used or activated. After a certain number of uses, the parts of the device can become worn and tolerances between parts exceeded. For instance, the smart battery assembly 486 can sense the number of button pushes received by the handle assembly 482 and can determine when a maximum number of button pushes has been met or exceeded. The smart battery assembly 486 can also monitor an impedance of the button mechanism which can change, for instance, if the handle gets contaminated, for example, with saline.

(261) This wear can lead to an unacceptable failure during a procedure. In some aspects, the smart battery assembly 486 can recognize which parts are combined together in a device and even how many uses a part has experienced. For instance, if the smart battery assembly 486 is a smart battery according to the present disclosure, it can identify the handle assembly 482, the waveguide shaft assembly 490, as well as the ultrasonic transducer/generator assembly 484, well before the user attempts use of the composite device. The memory 497 within the smart battery assembly 486 can, for example, record a time when the ultrasonic transducer/generator assembly 484 is operated, and how, when, and for how long it is operated. If the ultrasonic transducer/generator assembly 484 has an individual identifier, the smart battery assembly 486 can keep track of uses of the ultrasonic transducer/generator assembly 484 and refuse to supply power to that the ultrasonic transducer/generator assembly 484 once the handle assembly 482 or the ultrasonic transducer/generator assembly 484 exceeds its maximum number of uses. The ultrasonic transducer/generator assembly 484, the handle assembly 482, the waveguide shaft assembly 490, or other components can include a memory chip that records this information as well. In this way, any number of smart batteries in the smart battery assembly 486 can be used with any number of ultrasonic transducer/generator assemblies 484, staplers, vessel sealers, etc. and still be able to determine the total number of uses, or the total time of use (through use of the clock), or the total number of actuations, etc. of the ultrasonic transducer/generator assembly 484, the stapler, the vessel sealer, etc. or charge or discharge cycles. Smart functionality may reside outside the battery assembly 486 and may reside in the handle assembly 482, the ultrasonic transducer/generator assembly 484, and/or the shaft assembly 490, for example.

(262) When counting uses of the ultrasonic transducer/generator assembly 484, to intelligently terminate the life of the ultrasonic transducer/generator assembly 484, the surgical instrument accurately distinguishes between completion of an actual use of the ultrasonic transducer/generator assembly 484 in a surgical procedure and a momentary lapse in actuation of the ultrasonic transducer/generator assembly 484 due to, for example, a battery change or a temporary delay in the surgical procedure. Therefore, as an alternative to simply counting the number of activations of the ultrasonic transducer/generator assembly 484, a real-time clock (RTC) circuit can be implemented to keep track of the amount of time the ultrasonic transducer/generator assembly 484 actually is shut down. From the length of time measured, it can be determined through appropriate logic if the shutdown was significant enough to be considered the end of one actual use or if the shutdown was too short in time to be considered the end of one use. Thus, in some applications, this method may be a more accurate determination of the useful life of the ultrasonic transducer/generator assembly 484 than a simple “activations-based” algorithm, which for example, may provide that ten “activations” occur in a surgical procedure and, therefore, ten activations should indicate that the counter is incremented by one. Generally, this type and system of internal clocking will prevent misuse of the device that is designed to deceive a simple “activations-based” algorithm and will prevent incorrect logging of a complete use in instances

when there was only a simple de-mating of the ultrasonic transducer/generator assembly **484** or the smart battery assembly **486** that was required for legitimate reasons.

(263) Although the ultrasonic transducer/generator assemblies **484** of the surgical instrument **480** are reusable, in one aspect a finite number of uses may be set because the surgical instrument **480** is subjected to harsh conditions during cleaning and sterilization. More specifically, the battery pack is configured to be sterilized. Regardless of the material employed for the outer surfaces, there is a limited expected life for the actual materials used. This life is determined by various characteristics which could include, for example, the amount of times the pack has actually been sterilized, the time from which the pack was manufactured, and the number of times the pack has been recharged, to name a few. Also, the life of the battery cells themselves is limited. Software of the present disclosure incorporates inventive algorithms that verify the number of uses of the ultrasonic transducer/generator assembly **484** and smart battery assembly **486** and disables the device when this number of uses has been reached or exceeded. Analysis of the battery pack exterior in each of the possible sterilizing methods can be performed. Based on the harshest sterilization procedure, a maximum number of permitted sterilizations can be defined and that number can be stored in a memory of the smart battery assembly **486**. If it is assumed that a charger is non-sterile and that the smart battery assembly **486** is to be used after it is charged, then the charge count can be defined as being equal to the number of sterilizations encountered by that particular pack.

(264) In one aspect, the hardware in the battery pack may be disabled to minimize or eliminate safety concerns due to continuous drain in from the battery cells after the pack has been disabled by software. A situation can exist where the battery's internal hardware is incapable of disabling the battery under certain low voltage conditions. In such a situation, in an aspect, the charger can be used to “kill” the battery. Due to the fact that the battery microcontroller is OFF while the battery is in its charger, a non-volatile, System Management Bus (SMB) based electrically erasable programmable read only memory (EEPROM) can be used to exchange information between the battery microcontroller and the charger. Thus, a serial EEPROM can be used to store information that can be written and read even when the battery microcontroller is OFF, which is very beneficial when trying to exchange information with the charger or other peripheral devices. This example EEPROM can be configured to contain enough memory registers to store at least (a) a use-count limit at which point the battery should be disabled (Battery Use Count), (b) the number of procedures the battery has undergone (Battery Procedure Count), and/or (c) a number of charges the battery has undergone (Charge Count), to name a few. Some of the information stored in the EEPROM, such as the Use Count Register and Charge Count Register are stored in write-protected sections of the EEPROM to prevent users from altering the information. In an aspect, the use and counters are stored with corresponding bit-inverted minor registers to detect data corruption.

(265) Any residual voltage in the SMBus lines could damage the microcontroller and corrupt the SMBus signal. Therefore, to ensure that the SMBus lines of the battery controller **703** do not carry a voltage while the microcontroller is OFF, relays are provided between the external SMBus lines and the battery microcontroller board.

(266) During charging of the smart battery assembly **486**, an “end-of-charge” condition of the batteries within the smart battery assembly **486** is determined when, for example, the current flowing into the battery falls below a given threshold in a tapering manner when employing a constant-current/constant-voltage charging scheme. To accurately detect this “end-of-charge” condition, the battery microcontroller and buck boards are powered down and turned OFF during charging of the battery to reduce any current drain that may be caused by the boards and that may interfere with the tapering current detection. Additionally, the microcontroller and buck boards are powered down during charging to prevent any resulting corruption of the SMBus signal.

(267) With regard to the charger, in one aspect the smart battery assembly **486** is prevented from being inserted into the charger in any way other than the correct insertion position. Accordingly, the

exterior of the smart battery assembly **486** is provided with charger-holding features. A cup for holding the smart battery assembly **486** securely in the charger is configured with a contour-matching taper geometry to prevent the accidental insertion of the smart battery assembly **486** in any way other than the correct (intended) way. It is further contemplated that the presence of the smart battery assembly **486** may be detectable by the charger itself. For example, the charger may be configured to detect the presence of the SMBus transmission from the battery protection circuit, as well as resistors that are located in the protection board. In such case, the charger would be enabled to control the voltage that is exposed at the charger's pins until the smart battery assembly **486** is correctly seated or in place at the charger. This is because an exposed voltage at the charger's pins would present a hazard and a risk that an electrical short could occur across the pins and cause the charger to inadvertently begin charging.

(268) In some aspects, the smart battery assembly **486** can communicate to the user through audio and/or visual feedback. For example, the smart battery assembly **486** can cause the LEDs to light in a pre-set way. In such a case, even though the microcontroller in the ultrasonic transducer/generator assembly **484** controls the LEDs, the microcontroller receives instructions to be carried out directly from the smart battery assembly **486**.

(269) In yet a further aspect of the present disclosure, the microcontroller in the ultrasonic transducer/generator assembly **484**, when not in use for a predetermined period of time, goes into a sleep mode. Advantageously, when in the sleep mode, the clock speed of the microcontroller is reduced, cutting the current drain significantly. Some current continues to be consumed because the processor continues pinging waiting to sense an input. Advantageously, when the microcontroller is in this power-saving sleep mode, the microcontroller and the battery controller can directly control the LEDs. For example, a decoder circuit could be built into the ultrasonic transducer/generator assembly **484** and connected to the communication lines such that the LEDs can be controlled independently by the processor **493** while the ultrasonic transducer/generator assembly **484** microcontroller is "OFF" or in a "sleep mode." This is a power-saving feature that eliminates the need for waking up the microcontroller in the ultrasonic transducer/generator assembly **484**. Power is conserved by allowing the generator to be turned off while still being able to actively control the user-interface indicators.

(270) Another aspect slows down one or more of the microcontrollers to conserve power when not in use. For example, the clock frequencies of both microcontrollers can be reduced to save power. To maintain synchronized operation, the microcontrollers coordinate the changing of their respective clock frequencies to occur at about the same time, both the reduction and, then, the subsequent increase in frequency when full speed operation is required. For example, when entering the idle mode, the clock frequencies are decreased and, when exiting the idle mode, the frequencies are increased.

(271) In an additional aspect, the smart battery assembly **486** is able to determine the amount of usable power left within its cells and is programmed to only operate the surgical instrument to which it is attached if it determines there is enough battery power remaining to predictably operate the device throughout the anticipated procedure. For example, the smart battery assembly **486** is able to remain in a non-operational state if there is not enough power within the cells to operate the surgical instrument for 20 seconds. According to one aspect, the smart battery assembly **486** determines the amount of power remaining within the cells at the end of its most recent preceding function, e.g., a surgical cutting. In this aspect, therefore, the smart battery assembly **486** would not allow a subsequent function to be carried out if, for example, during that procedure, it determines that the cells have insufficient power. Alternatively, if the smart battery assembly **486** determines that there is sufficient power for a subsequent procedure and goes below that threshold during the procedure, it would not interrupt the ongoing procedure and, instead, will allow it to finish and thereafter prevent additional procedures from occurring.

(272) The following explains an advantage to maximizing use of the device with the smart battery

assembly **486** of the present disclosure. In this example, a set of different devices have different ultrasonic transmission waveguides. By definition, the waveguides could have a respective maximum allowable power limit where exceeding that power limit overstresses the waveguide and eventually causes it to fracture. One waveguide from the set of waveguides will naturally have the smallest maximum power tolerance. Because prior-art batteries lack intelligent battery power management, the output of prior-art batteries must be limited by a value of the smallest maximum allowable power input for the smallest/thinnest/most-frail waveguide in the set that is envisioned to be used with the device/battery. This would be true even though larger, thicker waveguides could later be attached to that handle and, by definition, allow a greater force to be applied. This limitation is also true for maximum battery power. For example, if one battery is designed to be used in multiple devices, its maximum output power will be limited to the lowest maximum power rating of any of the devices in which it is to be used. With such a configuration, one or more devices or device configurations would not be able to maximize use of the battery because the battery does not know the particular device's specific limits.

(273) In one aspect, the smart battery assembly **486** may be employed to intelligently circumvent the above-mentioned ultrasonic device limitations. The smart battery assembly **486** can produce one output for one device or a particular device configuration and the same smart battery assembly **486** can later produce a different output for a second device or device configuration. This universal smart battery surgical system lends itself well to the modern operating room where space and time are at a premium. By having a smart battery pack operate many different devices, the nurses can easily manage the storage, retrieval, and inventory of these packs. Advantageously, in one aspect the smart battery system according to the present disclosure may employ one type of charging station, thus increasing ease and efficiency of use and decreasing cost of surgical room charging equipment.

(274) In addition, other surgical instruments, such as an electric stapler, may have a different power requirement than that of the modular handheld ultrasonic surgical instrument **480**. In accordance with various aspects of the present disclosure, a smart battery assembly **486** can be used with any one of a series of surgical instruments and can be made to tailor its own power output to the particular device in which it is installed. In one aspect, this power tailoring is performed by controlling the duty cycle of a switched mode power supply, such as buck, buck-boost, boost, or other configuration, integral with or otherwise coupled to and controlled by the smart battery assembly **486**. In other aspects, the smart battery assembly **486** can dynamically change its power output during device operation. For instance, in vessel sealing devices, power management provides improved tissue sealing. In these devices, large constant current values are needed. The total power output needs to be adjusted dynamically because, as the tissue is sealed, its impedance changes. Aspects of the present disclosure provide the smart battery assembly **486** with a variable maximum current limit. The current limit can vary from one application (or device) to another, based on the requirements of the application or device.

(275) FIG. **26** is a detail view of a trigger **483** portion and switch of the ultrasonic surgical instrument **480** shown in FIG. **25**, according to one aspect of the present disclosure. The trigger **483** is operably coupled to the jaw member **495** of the end effector **492**. The ultrasonic blade **496** is energized by the ultrasonic transducer/generator assembly **484** upon activating the activation switch **485**. Continuing now with FIG. **25** and also looking to FIG. **26**, the trigger **483** and the activation switch **485** are shown as components of the handle assembly **482**. The trigger **483** activates the end effector **492**, which has a cooperative association with the ultrasonic blade **496** of the waveguide shaft assembly **490** to enable various kinds of contact between the end effector jaw member **495** and the ultrasonic blade **496** with tissue and/or other substances. The jaw member **495** of the end effector **492** is usually a pivoting jaw that acts to grasp or clamp onto tissue disposed between the jaw and the ultrasonic blade **496**. In one aspect, an audible feedback is provided in the trigger that clicks when the trigger is fully depressed. The noise can be generated by a thin metal

part that the trigger snaps over while closing. This feature adds an audible component to user feedback that informs the user that the jaw is fully compressed against the waveguide and that sufficient clamping pressure is being applied to accomplish vessel sealing. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the trigger **483** to measure the force applied to the trigger **483** by the user. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the switch **485** button such that displacement intensity corresponds to the force applied by the user to the switch **485** button.

(276) The activation switch **485**, when depressed, places the modular handheld ultrasonic surgical instrument **480** into an ultrasonic operating mode, which causes ultrasonic motion at the waveguide shaft assembly **490**. In one aspect, depression of the activation switch **485** causes electrical contacts within a switch to close, thereby completing a circuit between the smart battery assembly **486** and the ultrasonic transducer/generator assembly **484** so that electrical power is applied to the ultrasonic transducer, as previously described. In another aspect, depression of the activation switch **485** closes electrical contacts to the smart battery assembly **486**. Of course, the description of closing electrical contacts in a circuit is, here, merely an example general description of switch operation. There are many alternative aspects that can include opening contacts or processor-controlled power delivery that receives information from the switch and directs a corresponding circuit reaction based on the information.

(277) FIG. **27** is a fragmentary, enlarged perspective view of an end effector **492**, according to one aspect of the present disclosure, from a distal end with a jaw member **495** in an open position. Referring to FIG. **27**, a perspective partial view of the distal end **498** of the waveguide shaft assembly **490** is shown. The waveguide shaft assembly **490** includes an outer tube **494** surrounding a portion of the waveguide. The ultrasonic blade **496** portion of the waveguide **499** protrudes from the distal end **498** of the outer tube **494**. It is the ultrasonic blade **496** portion that contacts the tissue during a medical procedure and transfers its ultrasonic energy to the tissue. The waveguide shaft assembly **490** also includes a jaw member **495** that is coupled to the outer tube **494** and an inner tube (not visible in this view). The jaw member **495**, together with the inner and outer tubes and the ultrasonic blade **496** portion of the waveguide **499**, can be referred to as an end effector **492**. As will be explained below, the outer tube **494** and the non-illustrated inner tube slide longitudinally with respect to each other. As the relative movement between the outer tube **494** and the non-illustrated inner tube occurs, the jaw member **495** pivots upon a pivot point, thereby causing the jaw member **495** to open and close. When closed, the jaw member **495** imparts a pinching force on tissue located between the jaw member **495** and the ultrasonic blade **496**, insuring positive and efficient blade-to-tissue contact.

(278) FIG. **28** illustrates a modular shaft assembly **110** and end effector **112** portions of the surgical instrument **100**, according to one aspect of the present disclosure. The shaft assembly **110** comprises an outer tube **144**, an inner tube **147**, and an ultrasonic transmission waveguide **145**. The shaft assembly **110** is removably mounted to the handle assembly **102**. The inner tube **147** is slidably received within the outer tube **144**. The ultrasonic transmission waveguide **145** is positioned within the inner tube **147**. The jaw member **114** of the end effector **112** is pivotally coupled to the outer tube **144** at a pivot point **151**. The jaw member **114** also is coupled to inner tube **147** by a pin **153** such that as the inner tube **147** slides within the slot **155**, the jaw member opens and closes. In the illustrated configuration, the inner tube **147** is in its distal position and the jaw member **114** is open. To close the jaw member **114**, the inner tube **147** is retracted in the proximal direction **157** and to open the jaw member is advanced in the distal direction **159**. The proximal end of the shaft assembly **110** comprises a jaw member tube (e.g., inner tube)/spring assembly **141**. A spring **139** is provided to apply a constant force control mechanism for use with different shaft assemblies, motor closures to control constant force closures, two bar mechanism to drive closure systems, cam lobes to push and pull closure system, drive screw designs to drive closure or wave spring designs to control constant force.

(279) FIG. 29 is a detail view of the inner tube/spring assembly 141. A closure mechanism 149 is operably coupled to the trigger 108 (FIGS. 1-3). Accordingly, as the trigger 108 is squeezed, the inner tube 143 is retracted in the proximal direction 157 to close the jaw member 114. Accordingly, as the trigger 108 is released, the inner tube 143 is advanced in the distal direction 159 to open the jaw member 114.

(280) For a more detailed description of a combination ultrasonic/electrosurgical instrument, reference is made to U.S. Pat. No. 9,107,690, which is herein incorporated by reference.

(281) FIG. 30 illustrates a modular battery powered handheld combination ultrasonic/electrosurgical instrument 500, according to one aspect of the present disclosure. FIG. 31 is an exploded view of the surgical instrument 500 shown in FIG. 30, according to one aspect of the present disclosure. With reference now to FIGS. 30 and 31, the surgical instrument 500 comprises a handle assembly 502, an ultrasonic transducer/RF generator assembly 504, a battery assembly 506, a shaft assembly 510, and an end effector 512. The ultrasonic transducer/RF generator assembly 504, battery assembly 506, and shaft assembly 510 are modular components that are removably connectable to the handle assembly 502. The handle assembly 502 also comprises a motor assembly 560. The surgical instrument 500 is configured to use both ultrasonic vibration and electrosurgical high-frequency current to carry out surgical coagulation/cutting treatments on living tissue, and uses high-frequency current to carry out a surgical coagulation treatment on living tissue. The ultrasonic vibrations and the high-frequency (e.g., RF) current can be applied independently or in combination according to algorithms or user input control.

(282) The ultrasonic transducer/RF generator assembly 504 comprises a housing 548, a display 576, such as an LCD display, for example, an ultrasonic transducer 530, an electrical circuit 177 (FIGS. 4, 10 and/or electrical circuit 300 in FIG. 14), and a electrical circuit 702 (FIG. 34) configured to drive an RF electrode and forms a portion of an RF generator circuit. The shaft assembly 510 comprises an outer tube 544 an ultrasonic transmission waveguide 545, and an inner tube (not shown). The end effector 512 comprises a jaw member 514 and an ultrasonic blade 516. The jaw member 514 comprises an electrode 515 that is coupled to an RF generator circuit. The ultrasonic blade 516 is the distal end of the ultrasonic transmission waveguide 545. The jaw member 514 is pivotally rotatable to grasp tissue between the jaw member 514 and the ultrasonic blade 516. The jaw member 514 is operably coupled to a trigger 508. The trigger 508 functions to close the jaw member 514 when the trigger 508 is squeezed and to open the jaw member 514 when the trigger 508 is released to release the tissue. In a one-stage trigger configuration, the trigger 508 is squeezed to close the jaw member 514 and, once the jaw member 514 is closed, a first switch 521a of a switch section is activated to energize the RF generator to seal the tissue. After the tissue is sealed, a second switch 521b of the switch section 520 is activated to energize the ultrasonic generator to cut the tissue. In various aspects, the trigger 508 may be a two-stage, or a multi-stage, trigger. In a two-stage trigger configuration, during the first stage, the trigger 508 is squeezed part of the way to close the jaw member 514 and, during the second stage, the trigger 508 is squeezed the rest of the way to energize the RF generator circuit to seal the tissue. After the tissue is sealed, one of the switches 521a, 521b can be activated to energize the ultrasonic generator to cut the tissue. After the tissue is cut, the jaw member 514 is opened by releasing the trigger 508 to release the tissue. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the trigger 508 to measure the force applied to the trigger 508 by the user. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the switch 520 button such that displacement intensity corresponds to the force applied by the user to the switch 520 button.

(283) The battery assembly 506 is electrically connected to the handle assembly 502 by an electrical connector 532. The handle assembly 502 is provided with a switch section 520. A first switch 520a and a second switch 520b are provided in the switch section 520. The RF generator is activated by actuating the first switch 520a and the ultrasonic blade 516 is activated by actuating the second switch 520b. Accordingly, the first switch 520a energizes the RF circuit to drive high-

frequency current through the tissue to form a seal and the second switch **520b** energizes the ultrasonic transducer **530** to vibrate the ultrasonic blade **516** and cut the tissue.

(284) A rotation knob **518** is operably coupled to the shaft assembly **510**. Rotation of the rotation knob **518** $\pm 360^\circ$ in the direction indicated by the arrows **526** causes an outer tube **544** to rotate $\pm 360^\circ$ in the respective direction of the arrows **528**. In one aspect, another rotation knob **522** may be configured to rotate the jaw member **514** while the ultrasonic blade **516** remains stationary and the rotation knob **518** rotates the outer tube **144** $\pm 360^\circ$. The outer tube **144** may have a diameter D.sub.1 ranging from 5 mm to 10 mm, for example.

(285) FIG. **32** is a partial perspective view of a modular battery powered handheld combination ultrasonic/RF surgical instrument **600**, according to one aspect of the present disclosure. The surgical instrument **600** is configured to use both ultrasonic vibration and high-frequency current to carry out surgical coagulation/cutting treatments on living tissue, and uses high-frequency current to carry out a surgical coagulation treatment on living tissue. The ultrasonic vibrations and the high-frequency (e.g., RF) current can be applied independently or in combination according to algorithms or user input control. The surgical instrument **600** comprises a handle assembly **602**, an ultrasonic transducer/RF generator assembly **604**, a battery assembly **606**, a shaft assembly (not shown), and an end effector (not shown). The ultrasonic transducer/RF generator assembly **604**, battery assembly **606**, and shaft assembly are modular components that are removably connectable to the handle assembly **602**. A trigger **608** is operatively coupled to the handle assembly **602**. As previously described, the trigger operates the end effector.

(286) The ultrasonic transducer/RF generator assembly **604** comprises a housing **648**, a display **676**, such as an LCD display, for example. The display **676** provides a visual display of surgical procedure parameters such as tissue thickness, status of seal, status of cut, tissue thickness, tissue impedance, algorithm being executed, battery capacity, energy being applied (either ultrasonic vibration or RF current), among other parameters. The ultrasonic transducer/RF generator assembly **604** also comprises two visual feedback indicators **678**, **679** to indicate the energy modality currently being applied in the surgical procedure. For example, one indicator **678** shows when RF energy is being used and another indicator **679** shows when ultrasonic energy is being used. It will be appreciated that when both energy modalities RF and ultrasonic are being applied, both indicators will show this condition. The surgical instrument **600** also comprises an ultrasonic transducer, an ultrasonic generator circuit and/or electrical circuit, a shaft assembly, and an end effector comprising a jaw member and an ultrasonic blade, the modular components being similar to those described in connection with FIGS. **30** and **31** and the description will not be repeated here for conciseness and clarity of disclosure.

(287) The battery assembly **606** is electrically connected to the handle assembly **602** by an electrical connector. The handle assembly **602** is provided with a switch section **620**. A first switch **620a** and a second switch **620b** are provided in the switch section **620**. The ultrasonic blade is activated by actuating the first switch **620a** and the RF generator is activated by actuating the second switch **620b**. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the trigger **608** to measure the force applied to the trigger **608** by the user. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the switch **620** button such that displacement intensity corresponds to the force applied by the user to the switch **620** button.

(288) A rotation knob **618** is operably coupled to the shaft assembly. Rotation of the rotation knob **618** $\pm 360^\circ$ causes an outer tube to rotate $\pm 360^\circ$ in the respective direction, as described herein in connection with FIGS. **30** and **31**. In one aspect, another rotation knob may be configured to rotate the jaw member while the ultrasonic blade remains stationary and the rotation knob **618** rotates the outer tube $\pm 360^\circ$. A button **673** is used to connect and retain the shaft assembly to the handle assembly **602**. Another slide switch **675** is used to lock in and release the ultrasonic transducer/RF generator assembly **604**.

(289) In one aspect, the surgical instrument **500, 600** includes a battery powered advanced energy (ultrasonic vibration plus high-frequency current) with driver amplification broken into multiple stages. The different stages of amplification may reside in different modular components of the surgical instrument **500, 600** such as the handle assembly **502, 602** ultrasonic transducer/RF generator assembly **504, 604**, battery assembly **506, 606**, shaft assembly **510**, and/or the end effector **112**. In one aspect, the ultrasonic transducer/RF generator assembly **504, 604** may include an amplification stage in the ultrasonic transducer and/or RF electronic circuits within the housing **548, 648** and different ratios of amplification based on the energy modality associated with the particular energy mode. The final stage may be controlled via signals from the electronic system of the surgical instrument **100** located in the handle assembly **502, 602** and/or the battery assembly **506, 606** through a bus structure, such as I.sup.2C, as previously described. Final stage switches system may be employed to apply power to the transformer and blocking capacitors to form the RF waveform. Measurements of the RF output, such as voltage and current, are fed back to the electronic system over the bus. The handle assembly **502, 602** and/or battery assembly **506, 606** may contain the majority of the primary amplification circuits including any electrical isolation components, motor control, and waveform generator. The two differing ultrasonic transducers (e.g., ultrasonic transducer **130, 130'** shown in FIGS. **8** and **9**) and the RF transducer contain the electronics to utilize the preconditions generator signals and perform the final conditioning to power different frequency transducers of RF signals in the desired frequency ranges and amplitudes. This minimizes the weight size and cost of the electronics residing only in the transducers themselves. It also allows the primary processor boards to occupy the areas of the handle that have the most useful space which is rarely where the transducer is, due to its size. It also allows the electronics to be divided in such a way as the high wear high duty cycle elements could be only connectively attached to the primary electronics enabling it to be more serviceable and repairable since the system is designed for high repeated use before disposal.

(290) The surgical instruments **500, 600** described in connection with FIGS. **30-32** are configured to use high-frequency current to carry out surgical coagulation/cutting treatments on living tissue, and uses high-frequency current to carry out a surgical coagulation treatment on living tissue. Accordingly, additional structural and functional components to carry out this additional functionality will be described hereinbelow in connection with FIGS. **33-44**.

(291) The structural and functional aspects of the battery assembly **506, 606** are similar to those of the battery assembly **106** for the surgical instrument **100** described in connection with FIGS. **1, 2**, and **16-24**, including the battery circuits described in connection with FIGS. **20-24**. Accordingly, for conciseness and clarity of disclosure, such the structural and functional aspects of the battery assembly **106** are incorporated herein by reference and will not be repeated here. Similarly, unless otherwise noted, the structural and functional aspects of the shaft assembly **510** are similar to those of the shaft assembly **110** for the surgical instrument **100** described in connection with FIGS. **1-3**. Accordingly, for conciseness and clarity of disclosure, such the structural and functional aspects of the shaft assembly **110** are incorporated herein by reference and will not be repeated here.

Furthermore, the structural and functional aspects of the ultrasonic transducer **530** generator circuits are similar to those of the ultrasonic transducer **130** generator circuits for the surgical instrument **100** described in connection with FIGS. **1, 2**, and **4-15**. Accordingly, for conciseness and clarity of disclosure, such the structural and functional aspects of the ultrasonic transducer **130** and generator circuits are incorporated herein by reference and will not be repeated here.

Furthermore, the surgical instruments **500, 600** include the circuits described in connection with FIGS. **12-15**, including, for example, the control circuit **210** described in connection with FIG. **14** and the electrical circuit **300** described in connection with FIG. **15**. Accordingly, for conciseness and clarity of disclosure, the description of the circuits described in connection with FIGS. **12-15** is incorporated herein by reference and will not be repeated here.

(292) Turning now to FIG. **33**, there is shown a nozzle **700** portion of the surgical instruments **500**,

600 described in connection with FIGS. **30-32**, according to one aspect of the present disclosure. The nozzle **700** contains an electrical circuit **702** configured to drive the high-frequency RF current to an electrode located in the end effector as described hereinbelow in connection with FIGS. **38-44**. The electrical circuit **702** is coupled to the primary winding of a transformer **704**. The positive side of the secondary winding of the transformer **704** is coupled to series connected first and second blocking capacitors **706, 708**. The load side of the second blocking capacitor **708** is coupled to the positive RF(+) terminal which is coupled to the positive side of the end effector electrode. The negative side of the secondary winding of the transformer **704** is coupled to the negative RF(-) terminal, otherwise referred to as ground. It will be appreciated that the RF(-) or ground terminal of the RF energy circuit is coupled to an outer tube **744**, which is formed of an electrically conductive metal. Accordingly, in use, high-frequency current is conducted from the end effector electrode RF(+), through the tissue, and returns through the negative electrode RF(-).

(293) With reference now also to FIGS. **30, 31**, in one aspect, the outer tube **744** is operably coupled to the jaw member **514** portion of the end effector **512** such that the jaw member **514** opens when the outer tube **744** is advanced in the distal direction **722** and the jaw member **514** closes when the outer tube **744** is retracted in the proximal direction **724**. Although not shown in FIG. **33**, the outer tube **744** is operably coupled to the trigger **508**, which is used to open and close the jaw member **514** portion of the end effector **512**. Examples of actuation mechanisms for use with ultrasonic surgical instruments as described herein are disclosed in U.S. Patent Application Publication No. 2006/0079879 and U.S. Patent Application Publication No. 2015/0164532, now U.S. Pat. No. 9,724,120, each of which is herein incorporated by reference.

(294) Still with reference to FIGS. **30, 31**, and **33**, in one aspect, an inner tube **714** is slidably disposed within the outer tube **744**. The inner tube **714** is operably coupled to the jaw member **514** to rotate the jaw member **514** while maintaining the ultrasonic blade **516** stationary. In the aspect shown in FIGS. **30** and **31** the inner tube **714** is rotated by the rotation knob **522**. In the aspect shown in FIG. **33**, a motor **719** may be provided within the handle assembly **502** to engage a gear **721** on the proximal end of the outer tube **744**, optionally through an idler gear **725**.

(295) Still with reference to FIGS. **30, 31**, and **33**, in one aspect, an inner electrically insulative (e.g., rubber, plastic) tube **716** is slidably disposed within the inner tube **714**. A flex circuit **728** may be disposed within the inner electrically insulative tube **716** to electrically couple energy and sensor circuits to the end effector **512**. For example, the jaw member **514** may comprise an electrode coupled to conductors in the flex circuit **728**. In other aspects, the end effector **512**, jaw member **514**, or the ultrasonic blade **516** may comprise various sensors or other electrical elements that can be interconnected to electrical circuits and components in the shaft assembly **510**, the handle assembly **502**, the ultrasonic transducer/RF generator assembly **504**, and/or the battery assembly **506**, for example.

(296) Still with reference to FIGS. **30, 31**, and **33**, in one aspect, the ultrasonic transmission waveguide **545** (shown in FIG. **32** only; not shown in FIG. **33** for clarity) is disposed within the inner electrically insulative tube **716**. In one aspect, the positive electrode RF(+) of the electrical circuit **702** is electrically coupled to the ultrasonic transmission waveguide **545** and the negative electrode RF(-) of the electrical circuit **702** is electrically coupled to an electrode disposed in the jaw member **514**, which is electrically coupled to the outer tube **744**. In operation, after tissue is grasped between the ultrasonic blade **516** and the jaw member **514**, control circuits of the surgical instrument **500** can execute various algorithms to seal and the cut the tissue. The ultrasonic vibrations and high-frequency energy may be applied to the tissue in accordance with monitored tissue conditions such as tissue impedance, friction, and the like. In some situations, high-frequency current is applied to the tissue through the ultrasonic blade **516** and back to the outer tube **744** return path. The tissue impedance is monitored and when a tissue seal is formed, as may be determined by the tissue impedance, the ultrasonic blade **516** is mechanically energized to induce vibrational energy into the tissue to cut the tissue. In other aspects ultrasonic vibrations and

high-frequency may be applied by pulsing these energy modalities, applying the energy modalities alternatively or simultaneously. In somewhat unique situations, an algorithm can detect when the tissue impedance is extremely low to deliver energy to the tissue. In response, the algorithm energizes the ultrasonic blade **516** mechanically to apply vibratory energy to the tissue until such time that the impedance rises above a threshold suitable for the application of the high-frequency current. Upon reaching this threshold, the algorithm switches energy delivery mode to high-frequency current to seal the tissue.

(297) FIG. **34** is a schematic diagram of one aspect of an electrical circuit **702** configured to drive a high-frequency current (RF), according to one aspect of the present disclosure. The electrical circuit **702** comprises an analog multiplexer **580**. The analog multiplexer **580** multiplexes various signals from the upstream channels SCL-A/SDA-A such as RF, battery, and power control circuit. A current sensor **582** is coupled in series with the return or ground leg of the power supply circuit to measure the current supplied by the power supply. A field effect transistor (FET) temperature sensor **584** provides the ambient temperature. A pulse width modulation (PWM) watchdog timer **588** automatically generates a system reset if the main program neglects to periodically service it. It is provided to automatically reset the electrical circuit **702** when it hangs or freezes because of a software or hardware fault. It will be appreciated that the electrical circuit **702** may be configured for driving RF electrodes or for driving the ultrasonic transducer **130** as described in connection with FIG. **11**, for example. Accordingly, with reference now back to FIG. **34**, the electrical circuit **702** can be used to drive both ultrasonic and RF electrodes interchangeably.

(298) A drive circuit **586** provides left and right RF energy outputs. A digital signal that represents the signal waveform is provided to the SCL-A/SDA-A inputs of the analog multiplexer **580** from a control circuit, such as the control circuit **210** (FIG. **14**). A digital-to-analog converter **590** (DAC) converts the digital input to an analog output to drive a PWM circuit **592** coupled to an oscillator **594**. The PWM circuit **592** provides a first signal to a first gate drive circuit **596a** coupled to a first transistor output stage **598a** to drive a first RF+ (Left) energy output. The PWM circuit **592** also provides a second signal to a second gate drive circuit **596b** coupled to a second transistor output stage **598b** to drive a second RF- (Right) energy output. A voltage sensor **599** is coupled between the RF Left/RF output terminals to measure the output voltage. The drive circuit **586**, the first and second drive circuits **596a**, **596b**, and the first and second transistor output stages **598a**, **598b** define a first stage amplifier circuit. In operation, the control circuit **210** (FIG. **14**) generates a digital waveform **1800** (FIG. **67**) employing circuits such as direct digital synthesis (DDS) circuits **1500**, **1600** (FIGS. **65** and **66**). The DAC **590** receives the digital waveform **1800** and converts it into an analog waveform, which is received and amplified by the first stage amplifier circuit.

(299) FIG. **35** is a schematic diagram of the transformer **704** coupled to the electrical circuit **702** shown in FIG. **34**, according to one aspect of the present disclosure. The RF Left/RF input terminals (primary winding) of the transformer **704** are electrically coupled to the RF Left/RF output terminals of the electrical circuit **702**. One side of the secondary winding is coupled in series with first and second blocking capacitors **706**, **708**. The second blocking capacitor is coupled to the RF+ **574a** terminal. The other side of the secondary winding is coupled to the RF- **574b** terminal. As previously discussed, the RF+ **574a** output is coupled to the ultrasonic blade **516** (FIG. **30**) and the RF- **574b** ground terminal is coupled to the outer tube **544** (FIG. **30**). In one aspect, the transformer **166** has a turns-ratio of $n1:n2$ of 1:50.

(300) FIG. **36** is a schematic diagram of a circuit **710** comprising separate power sources for high power energy/drive circuits and low power circuits, according to one aspect of the present disclosure. A power supply **712** includes a primary battery pack comprising first and second primary batteries **715**, **717** (e.g., Li-ion batteries) that are connected into the circuit **710** by a switch **718** and a secondary battery pack comprising a secondary battery **720** that is connected into the circuit by a switch **723** when the power supply **712** is inserted into the battery assembly. The secondary battery **720** is a sag preventing battery that has componentry resistant to gamma or other

radiation sterilization. For instance, a switch mode power supply **727** and optional charge circuit within the battery assembly can be incorporated to allow the secondary battery **720** to reduce the voltage sag of the primary batteries **715**, **717**. This guarantees full charged cells at the beginning of a surgery that are easy to introduce into the sterile field. The primary batteries **715**, **717** can be used to power the motor control circuits **726** and the energy circuits **732** directly. The power supply/battery pack **712** may comprise a dual type battery assembly including primary Li-ion batteries **715**, **717** and secondary NiMH batteries **720** with dedicated energy cells **720** to control the handle electronics circuits **730** from dedicated energy cells **715**, **717** to run the motor control circuits **726** and the energy circuits **732**. In this case the circuit **710** pulls from the secondary batteries **720** involved in driving the handle electronics circuits **730** when the primary batteries **715**, **717** involved in driving the energy circuits **732** and/or motor control circuits **726** are dropping low. In one various aspect, the circuit **710** may include a one way diode that would not allow for current to flow in the opposite direction (e.g., from the batteries involved in driving the energy and/or motor control circuits to the batteries involved in driving the electronics circuits).

(301) Additionally, a gamma friendly charge circuit may be provided that includes a switch mode power supply **727** using diodes and vacuum tube components to minimize voltage sag at a predetermined level. With the inclusion of a minimum sag voltage that is a division of the NiMH voltages (3 NiMH cells) the switch mode power supply **727** could be eliminated. Additionally a modular system may be provided wherein the radiation hardened components are located in a module, making the module sterilizable by radiation sterilization. Other non-radiation hardened components may be included in other modular components and connections made between the modular components such that the componentry operates together as if the components were located together on the same circuit board. If only two NiMH cells are desired the switch mode power supply **727** based on diodes and vacuum tubes allows for sterilizable electronics within the disposable primary battery pack.

(302) Turning now to FIG. **37**, there is shown a control circuit **800** for operating a battery **801** powered RF generator circuit **802** for use with the surgical instrument **500** shown in FIGS. **30** and **31**, according to one aspect of the present disclosure. The surgical instrument **500** is configured to use both ultrasonic vibration and high-frequency current to carry out surgical coagulation/cutting treatments on living tissue, and uses high-frequency current to carry out a surgical coagulation treatment on living tissue.

(303) FIG. **37** illustrates a control circuit **800** that allows a dual generator system to switch between the RF generator circuit **802** and the ultrasonic generator circuit **820** (similar to the electrical circuit **177** shown in FIGS. **11** and **12**) energy modalities for the surgical instrument **500** shown in FIGS. **30** and **31**. In one aspect, a current threshold in an RF signal is detected. When the impedance of the tissue is low the high-frequency current through tissue is high when RF energy is used as the treatment source for the tissue. According to one aspect, a visual indicator **812** or light located on the surgical instrument **500** may be configured to be in an on-state during this high current period. When the current falls below a threshold, the visual indicator **812** is in an off-state. Accordingly, a photo-transistor **814** may be configured to detect the transition from an on-state to an off-state and disengages the RF energy as shown in the control circuit **800** shown in FIG. **37**. Therefore, when the energy button is released and the energy switch **826** is opened, the control circuit **800** is reset and both the RF and ultrasonic generator circuits **802**, **820** are held off.

(304) With reference to FIGS. **30-33** and **37**, in one aspect, a method of managing an RF generator circuit **802** and ultrasound generator circuit **820** is provided. As previously described the RF generator circuit **802** and/or the ultrasound generator circuit **820** may be located in the handle assembly **502**, the ultrasonic transducer/RF generator assembly **504**, the battery assembly **506**, the shaft assembly **510**, and/or the nozzle **700**. The control circuit **800** is held in a reset state if the energy switch **826** is off (e.g., open). Thus, when the energy switch **826** is opened, the control circuit **800** is reset and both the RF and ultrasonic generator circuits **802**, **820** are turned off. When

the energy switch **826** is squeezed and the energy switch **826** is engaged (e.g., closed), RF energy is delivered to the tissue and a visual indicator **812** operated by a current sensing step-up transformer **804** will be lit while the tissue impedance is low. The light from the visual indicator **812** provides a logic signal to keep the ultrasonic generator circuit **820** in the off state. Once the tissue impedance increases above a threshold and the high-frequency current through the tissue decreases below a threshold, the visual indicator **812** turns off and the light transitions to an off-state. A logic signal generated by this transition turns off the relay **808**, whereby the RF generator circuit **802** is turned off and the ultrasonic generator circuit **820** is turned on, to complete the coagulation and cut cycle. (305) Still with reference to FIGS. **30-33** and **37**, in one aspect, the dual generator circuit **802**, **820** configuration employs an on-board RF generator circuit **802**, which is battery **801** powered, for one modality and a second, on-board ultrasound generator circuit **820**, which may be on-board in the handle assembly **502**, battery assembly **506**, shaft assembly **510**, nozzle **700**, and/or the ultrasonic transducer/RF generator assembly **504**. The ultrasonic generator circuit **820** also is battery **801** operated. In various aspects, the RF generator circuit **802** and the ultrasonic generator circuit **820** may be an integrated or separable component of the handle assembly **502**. According to various aspects, having the dual RF/ultrasonic generator circuits **802**, **820** as part of the handle assembly **502** may eliminate the need for complicated wiring in an environment where the surgical instrument **500**. The RF/ultrasonic generator circuits **802**, **820** may be configured to provide the full capabilities of an existing generator while utilizing the capabilities of a cordless generator system simultaneously.

(306) Either type of system can have separate controls for the modalities that are not communicating with each other. The surgeon activates the RF and Ultrasonic separately and at their discretion. Another approach would be to provide fully integrated communication schemes that share buttons, tissue status, instrument operating parameters (such as jaw closure, forces, etc.) and algorithms to manage tissue treatment. Various combinations of this integration can be implemented to provide the appropriate level of function and performance.

(307) In one aspect, the control circuit **800** includes a battery **801** powered RF generator circuit **802** comprising a battery as an energy source. As shown, RF generator circuit **802** is coupled to two electrically conductive surfaces referred to herein as electrodes **806a**, **806b** and is configured to drive the electrodes **806a**, **806b** with RF energy (e.g., high-frequency current). A first winding **810a** of a step-up transformer **804** is connected in series with one pole of the bipolar RF generator circuit **802** and the return electrode **806b**. In one aspect, the first winding **810a** and the return electrode **806b** are connected to the negative pole of the bipolar RF generator circuit **802**. The other pole of the bipolar RF generator circuit **802** is connected to the active electrode **806a** through a switch contact **809** of a relay **808**, or any suitable electromagnetic switching device comprising an armature which is moved by an electromagnet **836** to operate the switch contact **809**. The switch contact **809** is closed when the electromagnet **836** is energized and the switch contact **809** is open when the electromagnet **836** is de-energized. When the switch contact is closed, RF current flows through conductive tissue (not shown) located between the electrodes **806a**, **806b**. It will be appreciated, that in one aspect, the active electrode **806a** is connected to the positive pole of the bipolar RF generator circuit **802**.

(308) A visual indicator circuit **805** comprises a step-up transformer **804**, a series resistor **R2**, and a visual indicator **812**. The visual indicator **812** can be adapted for use with the surgical instrument **500** and other electrosurgical systems and tools, such as those described herein. The first winding **810a** of the step-up transformer **804** is connected in series with the return electrode **806b** and a second winding **810b** of the step-up transformer **804** is connected in series with a resistor **R2** and a visual indicator **812** comprising a type NE-2 neon bulb, for example.

(309) In operation, when the switch contact **809** of the relay **808** is open, the active electrode **806a** is disconnected from the positive pole of the bipolar RF generator circuit **802** and no current flows through the tissue, the return electrode **806b**, and the first winding **810a** of the step-up transformer

804. Accordingly, the visual indicator **812** is not energized and does not emit light. When the switch contact **809** of the relay **808** is closed, the active electrode **806a** is connected to the positive pole of the bipolar RF generator circuit **802** enabling current to flow through tissue, the return electrode **806b**, and the first winding **810a** of the step-up transformer **804** to operate on tissue, for example cut and cauterize the tissue.

(310) A first current flows through the first winding **810a** as a function of the impedance of the tissue located between the active and return electrodes **806a**, **806b** providing a first voltage across the first winding **810a** of the step-up transformer **804**. A stepped up second voltage is induced across the second winding **810b** of the step-up transformer **804**. The secondary voltage appears across the resistor **R2** and energizes the visual indicator **812** causing the neon bulb to light when the current through the tissue is greater than a predetermined threshold. It will be appreciated that the circuit and component values are illustrative and not limited thereto. When the switch contact **809** of the relay **808** is closed, current flows through the tissue and the visual indicator **812** is turned on.

(311) Turning now to the energy switch **826** portion of the control circuit **800**, when the energy switch **826** is open position, a logic high is applied to the input of a first inverter **828** and a logic low is applied of one of the two inputs of the AND gate **832**. Thus, the output of the AND gate **832** is low and the transistor **834** is off to prevent current from flowing through the winding of the electromagnet **836**. With the electromagnet **836** in the de-energized state, the switch contact **809** of the relay **808** remains open and prevents current from flowing through the electrodes **806a**, **806b**. The logic low output of the first inverter **828** also is applied to a second inverter **830** causing the output to go high and resetting a flip-flop **818** (e.g., a D-Type flip-flop). At which time, the Q output goes low to turn off the ultrasound generator circuit **820** circuit and the Q output goes high and is applied to the other input of the AND gate **832**.

(312) When the user presses the energy switch **826** on the instrument handle to apply energy to the tissue between the electrodes **806a**, **806b**, the energy switch **826** closes and applies a logic low at the input of the first inverter **828**, which applies a logic high to other input of the AND gate **832** causing the output of the AND gate **832** to go high and turns on the transistor **834**. In the on state, the transistor **834** conducts and sinks current through the winding of the electromagnet **836** to energize the electromagnet **836** and close the switch contact **809** of the relay **808**. As discussed above, when the switch contact **809** is closed, current can flow through the electrodes **806a**, **806b** and the first winding **810a** of the step-up transformer **804** when tissue is located between the electrodes **806a**, **806b**.

(313) As discussed above, the magnitude of the current flowing through the electrodes **806a**, **806b** depends on the impedance of the tissue located between the electrodes **806a**, **806b**. Initially, the tissue impedance is low and the magnitude of the current high through the tissue and the first winding **810a**. Consequently, the voltage impressed on the second winding **810b** is high enough to turn on the visual indicator **812**. The light emitted by the visual indicator **812** turns on the phototransistor **814**, which pulls the input of the inverter **816** low and causes the output of the inverter **816** to go high. A high input applied to the CLK of the flip-flop **818** has no effect on the Q or the Q outputs of the flip-flop **818** and Q output remains low and the Q output remains high. Accordingly, while the visual indicator **812** remains energized, the ultrasound generator circuit **820** is turned OFF and the ultrasonic transducer **822** and ultrasonic blade **824** are not activated.

(314) As the tissue between the electrodes **806a**, **806b** dries up, due to the heat generated by the current flowing through the tissue, the impedance of the tissue increases and the current therethrough decreases. When the current through the first winding **810a** decreases, the voltage across the second winding **810b** also decreases and when the voltage drops below a minimum threshold required to operate the visual indicator **812**, the visual indicator **812** and the phototransistor **814** turn off. When the phototransistor **814** turns off, a logic high is applied to the input of the inverter **816** and a logic low is applied to the CLK input of the flip-flop **818** to clock a

logic high to the Q output and a logic low to the Q output. The logic high at the Q output turns on the ultrasound generator circuit **820** to activate the ultrasonic transducer **822** and the ultrasonic blade **824** to initiate cutting the tissue located between the electrodes **806a**, **806b**. Simultaneously or near simultaneously with the ultrasound generator circuit **820** turning on, the Q output of the flip-flop **818** goes low and causes the output of the AND gate **832** to go low and turn off the transistor **834**, thereby de-energizing the electromagnet **836** and opening the switch contact **809** of the relay **808** to cut off the flow of current through the electrodes **806a**, **806b**.

(315) While the switch contact **809** of the relay **808** is open, no current flows through the electrodes **806a**, **806b**, tissue, and the first winding **810a** of the step-up transformer **804**. Therefore, no voltage is developed across the second winding **810b** and no current flows through the visual indicator **812**.

(316) The state of the Q and the Q outputs of the flip-flop **818** remain the same while the user squeezes the energy switch **826** on the instrument handle to maintain the energy switch **826** closed. Thus, the ultrasonic blade **824** remains activated and continues cutting the tissue between the jaws of the end effector while no current flows through the electrodes **806a**, **806b** from the bipolar RF generator circuit **802**. When the user releases the energy switch **826** on the instrument handle, the energy switch **826** opens and the output of the first inverter **828** goes low and the output of the second inverter **830** goes high to reset the flip-flop **818** causing the Q output to go low and turn off the ultrasound generator circuit **820**. At the same time, the Q output goes high and the circuit is now in an off state and ready for the user to actuate the energy switch **826** on the instrument handle to close the energy switch **826**, apply current to the tissue located between the electrodes **806a**, **806b**, and repeat the cycle of applying RF energy to the tissue and ultrasonic energy to the tissue as described above.

(317) FIG. **38** is a sectional view of an end effector **900**, according to one aspect of the present disclosure. The end effector **900** comprises an ultrasonic blade **902** and a jaw member **904**. The jaw member **904** has a channel-shaped groove **906** in which part of the end effector **900** is engaged, along an axial direction. The channel-shaped groove **906** has a wide channel shape with a wide opening in a section orthogonal to an axis of the jaw member **904**. The jaw member **904** is made of a conductive material, and an insulating member **910** is provided in a range where the ultrasonic blade **902** is in contact along the axial direction on a bottom surface portion **912** of the channel shape.

(318) The ultrasonic blade **902** has a rhombic shape partially cut out in the section orthogonal to the axial direction. The sectional shape of the ultrasonic blade **902** is a shape which is cut out in the direction orthogonal to a longer diagonal line of the rhombic shape as shown in FIG. **38**. The ultrasonic blade **902** with part of the rhombic shape cut out in the sectional shape has a trapezoidal portion **914** which is engaged in the channel-shaped groove **906** of the jaw member **904**. A portion in which part of the rhombic shape is not cut out in the sectional shape is an isosceles triangle portion **916** of the ultrasonic blade **902**.

(319) When the trigger of the handle assembly is closed, the ultrasonic blade **902** and the jaw member **904** are fitted to each other. When they are fitted, the bottom surface portion **912** of the channel-shaped groove **906** abuts on a top surface portion **918** of the trapezoidal portion **914** of the ultrasonic blade **902**, and two inner wall portions **920** of the channel-shaped groove **906** abut on inclined surface portions **922** of the trapezoidal portion **914**.

(320) Further, an apex portion **924** of the isosceles triangle portion **916** of the ultrasonic blade **902** is formed to be rounded, but the apex portion **924** has a slightly sharp angle.

(321) When the surgical instrument is used as a spatulate ultrasound treatment instrument, the ultrasonic blade **902** acts as an ultrasound vibration treatment portion, and the apex portion **924** and its peripheral portion (shown by the dotted line) particularly act as a scalpel knife to the tissue of the treatment object.

(322) Further, when the surgical instrument is used as a spatulate high-frequency treatment instrument, the apex portion **924** and its peripheral portion (shown by the dotted line) act as an

electric scalpel knife to the tissue of the treatment object.

(323) In one aspect, the bottom surface portion **912** and the inner wall portions **920**, and the top surface portion **918** and the inclined surface portions **922** act as the working surfaces of an ultrasound vibration.

(324) Further, in one aspect, the inner wall portions **920** and the inclined surface portions **922** act as the working surfaces of a bipolar high-frequency current.

(325) In one aspect, the surgical instrument may be used as a spatulate treatment instrument of simultaneous output of ultrasound and high-frequency current, the ultrasonic blade **902** acts as the ultrasound vibration treatment portion, and the apex portion **924** and its peripheral portion (shown by the dotted line) particularly act as an electrical scalpel knife to the tissue of the treatment object.

(326) Further, when the surgical instrument provides simultaneous output of ultrasound and high-frequency current, the bottom surface portion **912** and the top surface portion **918** act as the working surfaces of an ultrasound vibration, and the inner wall portions **920** and the inclined surface portions **922** act as the working surfaces of a bipolar high-frequency current.

(327) Consequently, according to the configuration of the treatment portion shown in FIG. **37**, excellent operability is provided not only in the case of use of the surgical instrument as an ultrasound treatment instrument or a high-frequency treatment instrument, but also in the case of use of the surgical instrument as an ultrasound treatment instrument or high-frequency current treatment instrument, and further in the case of use of the surgical instrument for the time of simultaneous output of ultrasound and high frequency.

(328) When the surgical instrument performs high-frequency current output or simultaneous output of high-frequency current and ultrasound, monopolar output may be enabled instead of a bipolar output as the high-frequency output.

(329) FIG. **39** is a sectional view of an end effector **930**, according to one aspect of the present disclosure. The jaw member **932** is made of a conductive material, and an insulating member **934** is provided along the axial direction on a bottom surface portion **936** of the channel shape.

(330) The ultrasonic blade **938** has a rhombic shape partially cut out in the section orthogonal to the axial direction. The sectional shape of the ultrasonic blade **938** is a shape in which part of the rhombic shape is cut out in the direction orthogonal to one diagonal line as shown in FIG. **39**. The ultrasonic blade **938** with part of the rhombic shape cut out in the sectional shape has a trapezoidal portion **940** which is engaged in a channel-shaped groove **942** of the jaw member **932**. A portion in which part of the rhombic shape is not cut out in the sectional shape is an isosceles triangle portion **944** of the end effector **900**.

(331) When the trigger of the handle assembly is closed, the ultrasonic blade **938** and the jaw member **906** are fitted to each other. When they are fitted, the bottom surface portion **936** of the channel-shaped groove **942** abuts on a top surface portion **946** of the trapezoidal portion **940** of the ultrasonic blade **938**, and two inner wall portions **954** of the channel-shaped groove **932** abut on inclined surface portions **948** of the trapezoidal portion **940**.

(332) Further, an apex portion **950** of the isosceles triangle portion **944** of the ultrasonic blade **938** is formed to be rounded, but an apex portion **952** of the inner side of the hook shape has a slightly sharp angle. An angle θ of the apex portion **952** is preferably 45° to 100° . 45° is a strength limit of the ultrasonic blade **938**. As above, the apex portion **952** of the ultrasonic blade **938** configures a protruding portion having a predetermined angle at the inner side of the hook-shaped portion, that is, an edge portion.

(333) The treatment portion in the hook shape is often used for dissection. The apex portion **952** of the end effector **930** becomes a working portion at the time of dissection. Since the apex portion **952** has the slightly sharp angle θ , the apex portion **952** is effective for dissection treatment.

(334) The ultrasonic blade **938** and the jaw member **932** shown in FIG. **39** perform the same operation as the ultrasonic blade **938** and the jaw member **932** shown in FIG. **38** at the time of ultrasound output, at the time of high-frequency output, and at the time of simultaneous output of

ultrasound and high frequency respectively, except for the aforementioned operation at the time of dissection.

(335) Referring now to FIGS. **40-43**, there is shown and end effector **1000** operably coupled to an insertion sheath **1001**, which is formed by an outer sheath **1002** and an inner sheath **1004**. The end effector **1000** comprises an ultrasonic blade **1006** and a jaw member **1014**. In the outer sheath **1002**, the outside of a conductive metal pipe is covered with an insulating resin tube. The inner sheath **1004** is a conductive metal pipe. The inner sheath **1004** can be axially moved back and forth relative to the outer sheath **1002**.

(336) The ultrasonic blade **1006** is made of a conductive material having high acoustic effects and biocompatibility, for example, a titanium alloy such as a Ti-6Al-4V alloy. In the ultrasonic blade **1006**, an insulating and elastic rubber lining **1008** is externally equipped in the position of nodes of the ultrasonic vibration. The rubber lining **1008** is disposed between the inner sheath **1004** and the ultrasonic blade **1006** in a compressed state. The ultrasonic blade **1006** is held to the inner sheath **1004** by the rubber lining **1008**. A clearance is maintained between the inner sheath **1004** and the ultrasonic blade **1006**.

(337) An abutting portion **1010** is formed by the part of the ultrasonic blade **1012** facing the jaw member **1014** at the distal end portion of the ultrasonic blade **1006**. Here, the ultrasonic blade **1012** is octagonal in its cross section perpendicular to the axial directions of the ultrasonic blade **1006**. An abutting surface **1016** is formed by one surface of the abutting portion **1010** facing the jaw member **1014**. A pair of electrode surfaces **1018** is formed by surfaces provided to the sides of the abutting surface **1016**.

(338) The jaw member **1014** is formed by a body member **1020**, an electrode member **1022**, a pad member **1024**, and a regulating member **1026** as a regulating section.

(339) The body member **1020** is made of a hard and conductive material. A proximal end portion of the body member **1020** constitutes a pivot connection portion **1028**. The pivot connection portion **1028** is pivotally connected to a distal end portion of the outer sheath **1002** via a pivot connection shaft **1030**. The pivot connection shaft **1030** extends in width directions perpendicular to the axial directions and the opening/closing directions. The body member **1020** can turn about the pivot connection shaft **1030** in the opening/closing directions relative to the outer sheath **1002**. A distal end portion of the inner sheath **1004** is pivotally connected to the pivot connection portion **1028** of the body member **1020** at a position provided to the distal side and the opening-direction side of the pivot connection shaft **1030**. If the movable handle is turned relative to the fixed handle in the handle unit, the inner sheath **1004** is moved back and forth relative to the outer sheath **1002**, and the body member **1020** is driven by the inner sheath **1004** to turn about the pivot connection shaft **1030** in the opening/closing directions relative to the outer sheath **1002**. In one aspect, a distal part of the body member **1020** constitutes a pair of pivot bearings **1032**. The pair of pivot bearings **1032** are in the form of plates which extend in the axial directions and which are perpendicular to the width directions, and are disposed apart from each other in the width directions.

(340) The electrode member **1022** is made of a hard and conductive material. The part of the electrode member **1022** provided on the opening-direction side constitutes a pivot support **1034**. An insertion hole **1036** is formed through the pivot support **1034** in the width directions. A pivot support shaft **1038** is inserted through the insertion hole **1036** and extends in the width directions. The pivot support **1034** is disposed between the pair of pivot bearings **1032** of the body member **1020**, and is pivotally supported on the pair of pivot bearings **1032** via the pivot support shaft **1038**. The electrode member **1022** can oscillate about the pivot support shaft **1038** relative to the body member **1020**. Further, the part of the electrode member **1022** provided on the closing-direction side constitutes an electrode section **1040**. The electrode section **1040** extends in the axial directions and projects to the sides in the width directions. A recessed groove **1042** which is open toward the closing direction extends in the axial directions in the part of the electrode section **1040** provided on the closing-direction side. Teeth are axially provided in the parts of the groove **1042**

provided in the closing direction side, thus forming a tooth portion **1044**. The side surfaces that define the groove **1042** constitute a pair of electrode receiving surfaces **1046** that are inclined from the closing direction toward the sides in the width directions. A recessed mating receptacle **1048** which is open toward the closing direction axially extends in a bottom portion that defines the groove **1042**. An embedding hole **1050** is formed through the pivot support **1034** of the electrode member **1022** in the opening/closing directions perpendicularly to the insertion hole **1036**. The embedding hole **1050** is open to the mating receptacle **1048**.

(341) The pad member **1024** is softer than the ultrasonic blade **1006**, and is made of an insulating material having biocompatibility such as polytetrafluorethylene. The pad member **1024** is mated with the mating receptacle **1048** of the electrode member **1022**. The part of the pad member **1024** provided on the closing-direction side protrudes from the electrode member **1022** to the closing direction, thus forming an abutting receptacle **1052**. In the cross section perpendicular to the axial directions, the abutting receptacle **1052** is in a recessed shape corresponding to the projecting shape of the abutting portion **1010** of the ultrasonic blade **1012**. When the jaw member **1014** is closed relative to the ultrasonic blade **1012**, the abutting portion **1010** of the ultrasonic blade **1012** abuts onto and engages with the abutting receptacle **1052** of the pad member **1024**. The pair of electrode surfaces **1018** of the ultrasonic blade **1012** are arranged parallel to the pair of electrode receiving surfaces **1046** of the electrode section **1040**, and a clearance is maintained between the electrode section **1040** and the ultrasonic blade **1012**.

(342) The regulating member **1026** is harder than the ultrasonic blade **1006**, and is made of an insulating high-strength material such as ceramics. The regulating pad member **1024** is pin-shaped. The regulating pad member **1024** is inserted into the embedding hole **1050** of the pivot support **1034** of the electrode member **1022**, protrudes toward the mating receptacle **1048** of the electrode section **1040**, and is embedded in the abutting receptacle **1052** of the pad member **1024** in the mating receptacle **1048**. A closing-direction end of the regulating member **1026** constitutes a regulating end **1054**. The regulating end **1054** does not protrude from the abutting receptacle **1052** to the closing direction, and is accommodated in the abutting receptacle **1052**. The insertion hole **1036** is also formed through the regulating member **1026**, and the pivot support shaft **1038** is inserted through the insertion hole **1036** of the regulating member **1026**.

(343) Here, the inner sheath **1004**, the body member **1020**, and the electrode member **1022** are electrically connected to one another, and constitute the first electrical path **1056** used in a high-frequency surgical treatment. The electrode section **1040** of the electrode member **1022** functions as one of bipolar electrodes used in a high-frequency surgical treatment. In one aspect, the ultrasonic blade **1006** constitutes the second electrical path **1058** used in the high-frequency treatment. The ultrasonic blade **1012** provided to the distal end portion of the ultrasonic blade **1006** functions as the other of the bipolar electrodes used in a high-frequency treatment. As described above, the ultrasonic blade **1006** is held to the inner sheath **1004** by the insulating rubber lining **1008**, and the clearance is maintained between the inner sheath **1004** and the ultrasonic blade **1006**. This prevents a short circuit between the inner sheath **1004** and the ultrasonic blade **1006**. When the jaw member **1014** is closed relative to the ultrasonic blade **1012**, the abutting portion **1010** of the ultrasonic blade **1012** abuts onto and engages with the abutting receptacle **1052** of the pad member **1024**. Thus, the pair of electrode surfaces **1018** of the ultrasonic blade **1012** are arranged parallel to the pair of electrode receiving surfaces **1046** of the electrode section **1040**, and the clearance is maintained between the electrode section **1040** and the ultrasonic blade **1012**. This prevents a short circuit between the electrode section **1040** and the ultrasonic blade **1012**.

(344) Referring to FIG. 44, the pad member **1024** is softer than the ultrasonic blade **1006**. Therefore, the abutting receptacle **1052** is worn by the ultrasonic blade **1012** in the case where the ultrasonic blade **1012** is ultrasonically vibrated when the jaw member **1014** is closed relative to the ultrasonic blade **1012** and the abutting portion **1010** of the ultrasonic blade **1012** abuts onto and engages with the abutting receptacle **1052** of the pad member **1024**. As the abutting receptacle **1052**

is worn, the clearance between the electrode section **1040** and the ultrasonic blade **1012** is gradually reduced when the abutting portion **1010** is in a frictional engagement with the abutting receptacle **1052**. When the abutting receptacle **1052** is worn more than a predetermined amount, the regulating end **1054** of the regulating member **1026** is exposed from the abutting receptacle **1052** in the closing direction. When the regulating end **1054** is exposed from the abutting receptacle **1052** in the closing direction, the regulating end **1054** contacts the ultrasonic blade **1012** before the electrode section **1040** contacts the ultrasonic blade **1012** if the jaw member **1014** is closed relative to the ultrasonic blade **1012**. As a result, the contact between the ultrasonic blade **1012** and the electrode section **1040** is regulated. Here, the electrode section **1040** and the ultrasonic blade **1012** are hard. Therefore, when the ultrasonically vibrated ultrasonic blade **1012** contacts the electrode section **1040**, the ultrasonic blade **1012** rapidly and repetitively comes in and out of contact with the electrode section **58**. When a high-frequency voltage is applied between the electrode section **1040** and the ultrasonic blade **1012**, sparking occurs between the ultrasonic blade **1012** and the electrode section **1040**. In one aspect, the contact between the ultrasonic blade **1012** and the electrode section **1040** is regulated by the regulating end **1054** of the regulating member **1026**, so that sparking is prevented. The regulating member **1026** is made of an insulating material, and is electrically insulated relative to the electrode member **1022**. Thus, if the ultrasonically vibrated ultrasonic blade **1012** contacts the regulating end **1054** of the regulating member **1026**, no sparking occurs between the regulating end **1054** and the ultrasonic blade **1012** even when the ultrasonic blade **1012** rapidly and repetitively comes in and out of contact with the regulating end **1054**. This prevents sparking between the ultrasonic blade **1012** and the jaw member **1014**.

(345) The regulating member **1026** is made of a high-strength material harder than the ultrasonic blade **1006**. Therefore, when the regulating end **1054** contacts the ultrasonically vibrated ultrasonic blade **1012**, the regulating member **1026** is not worn, and the ultrasonic blade **1006** cracks. In the surgical treatment system according to one aspect, when the abutting receptacle **1052** is worn more than a predetermined amount, the regulating end **1054** contacts the ultrasonic blade **1012** to intentionally crack the ultrasonic blade **1006**. By detecting this crack, the end of the life of the surgical treatment instrument is detected. Therefore, the position of the contact between the ultrasonic blade **1012** and the regulating end **1054** is set at the stress concentration region in the ultrasonic blade **1012** to ensure that the ultrasonic blade **1006** cracks when the regulating end **1054** contacts the ultrasonic blade **1012**. In a linear ultrasonic blade **1006**, stress concentrates in the positions of the nodes of the ultrasonic vibration, and a stress concentration region is located at the proximal end portion of the ultrasonic blade **1012**.

(346) For a more detailed description of a combination ultrasonic/electrosurgical instrument, reference is made to U.S. Pat. Nos. 8,696,666 and 8,663,223, each of which is herein incorporated by reference.

(347) FIG. **45** illustrates a modular battery powered handheld electrosurgical instrument **1100** with distal articulation, according to one aspect of the present disclosure. The surgical instrument **1100** comprises having a handle assembly **1102**, a knife drive assembly **1104**, a battery assembly **1106**, a shaft assembly **1110**, and an end effector **1112**. The end effector **1112** comprises a pair of jaw members **1114a**, **1114b** in opposing relationship affixed to a distal end thereof. The end effector **1112** is configured to articulate and rotate. FIG. **46** is an exploded view of the surgical instrument **1100** shown in FIG. **45**, according to one aspect of the present disclosure. The end effector **1112** for use with the surgical instrument **1100** for sealing and cutting tissue includes a pair of jaw members **1114a**, **1114b** that in opposing relationship and movable relative to each other to grasp tissue therebetween. A jaw member **1114a**, **1114b** includes a jaw housing and an electrically conductive surface **1116a**, **1116b**, e.g., electrodes, adapted to connect to a source of electrosurgical energy (RF source) such that the electrically conductive surfaces are capable of conducting electrosurgical energy through tissue held therebetween to effect a tissue seal. One of the electrically conductive surfaces **1116b** includes a channel defined therein and extending along a length thereof that

communicates with a drive rod **1145** connected to a motor disposed in the knife drive assembly **1104**. The knife is configured to translate and reciprocate along the channel to cut tissue grasped between the jaw members **1114a**, **1114b**.

(348) FIG. **47** is a perspective view of the surgical instrument **1100** shown in FIGS. **45** and **46** with a display located on the handle assembly **1102**, according to one aspect of the present disclosure. The handle assembly **1102** of the surgical instrument shown in FIGS. **45-47** comprises a motor assembly **1160** and a display assembly. The display assembly comprises a display **1176**, such as an LCD display, for example, which is removably connectable to a housing **1148** portion of the handle assembly **1102**. The display **1176** provides a visual display of surgical procedure parameters such as tissue thickness, status of seal, status of cut, tissue thickness, tissue impedance, algorithm being executed, battery capacity, among other parameters.

(349) FIG. **48** is a perspective view of the instrument shown in FIGS. **45** and **46** without a display located on the handle assembly **1102**, according to one aspect of the present disclosure. The handle assembly **1102** of the surgical instrument **1150** shown in FIG. **48** includes a different display assembly **1154** on a separate housing **1156**. With reference now to FIGS. **45-48**, the surgical instrument **1100**, **1150** is configured to use high-frequency (RF) current and a knife to carry out surgical coagulation/cutting treatments on living tissue, and uses high-frequency current to carry out a surgical coagulation treatment on living tissue. The high-frequency (RF) current can be applied independently or in combination with algorithms or user input control. The display assembly, battery assembly **1106**, and shaft assembly **1110** are modular components that are removably connectable to the handle assembly **1102**. A motor **1140** is located within the handle assembly **1102**. RF generator circuits and motor drive circuits are described herein in connection with FIGS. **34-37** and **50**, for example, is located within the housing **1148**.

(350) The shaft assembly **1110** comprises an outer tube **1144**, a knife drive rod **1145**, and an inner tube (not shown). The shaft assembly **1110** comprises an articulation section **1130** and a distal rotation section **1134**. The end effector **1112** comprises jaw members **1114a**, **1114b** in opposing relationship and a motor driven knife. The jaw member **1114a**, **1114b** comprises an electrically conductive surface **1116a**, **1116b** coupled to the RF generator circuit for delivering high-frequency current to tissue grasped between the opposed jaw members **1114a**, **1114b**. The jaw members **1114a**, **1114b** are pivotally rotatable about a pivot pin **1136** to grasp tissue between the jaw members **1114a**, **1114b**. The jaw members **1114a**, **1114b** are operably coupled to a trigger **1108** such that when the trigger **1108** is squeezed the jaw members **1114a**, **1114b** close to grasp tissue and when the trigger **1108** is released the jaw members **1114a**, **1114b** open to release tissue.

(351) The jaw members **1114a**, **1114b** are operably coupled to a trigger **1108** such that when the trigger **1108** is squeezed the jaw members **1114a**, **1114b** close to grasp tissue and when the trigger **1108** is released the jaw members **1114a**, **1114b** open to release tissue. In a one-stage trigger configuration, the trigger **1108** is squeezed to close the jaw members **1114a**, **1114b** and, once the jaw members **1114a**, **1114b** are closed, a first switch **1121a** of a switch section **1121** is activated to energize the RF generator to seal the tissue. After the tissue is sealed, a second switch **1121b** of the switch section **1120** is activated to advance a knife to cut the tissue. In various aspects, the trigger **1108** may be a two-stage, or a multi-stage, trigger. In a two-stage trigger configuration, during the first stage, the trigger **1108** is squeezed part of the way to close the jaw members **1114a**, **1114b** and, during the second stage, the trigger **1108** is squeezed the rest of the way to energize the RF generator circuit to seal the tissue. After the tissue is sealed, one of the first and second switches **1121a**, **1121b** can be activated to advance the knife to cut the tissue. After the tissue is cut, the jaw members **1114a**, **1114b** are opened by releasing the trigger **1108** to release the tissue. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the trigger **1108** to measure the force applied to the trigger **1108** by the user. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the switch section **1120** first and second switch **1121a**, **1121b** buttons such that displacement intensity corresponds to the force applied by the user

to the switch section **1120** first and second switch **1121a**, **1121b** buttons.

(352) The battery assembly **1106** is electrically connected to the handle assembly **1102** by an electrical connector **1132**. The handle assembly **1102** is provided with a switch section **1120**. A first switch **1121a** and a second switch **1121b** are provided in the switch section **1120**. The RF generator is energized by actuating the first switch **1121a** and the knife is activated by energizing the motor **1140** by actuating the second switch **1121b**. Accordingly, the first switch **1121a** energizes the RF circuit to drive the high-frequency current through the tissue to form a seal and the second switch **1121b** energizes the motor to drive the knife to cut the tissue. The structural and functional aspects of the battery assembly **1106** are similar to those of the battery assembly **106** for the surgical instrument **100** described in connection with FIGS. **1**, **2**, and **16-24**. Accordingly, for conciseness and clarity of disclosure, such the structural and functional aspects of the battery assembly **106** are incorporated herein by reference and will not be repeated here.

(353) A rotation knob **1118** is operably coupled to the shaft assembly **1110**. Rotation of the rotation knob **1118** $\pm 360^\circ$ in the direction indicated by the arrows **1126** causes the outer tube **1144** to rotate $\pm 360^\circ$ in the respective direction of the arrows **1119**. In one aspect, another rotation knob **1122** may be configured to rotate the end effector **1112** $\pm 360^\circ$ in the direction indicated by the arrows **1128** independently of the rotation of the outer tube **1144**. The end effector **1112** may be articulated by way of first and second control switches **1124a**, **1124b** such that actuation of the first control switch **1124a** articulates the end effector **1112** about a pivot **1138** in the direction indicated by the arrow **1132a** and actuation of the second control switch **1124b** articulates the end effector **1112** about the pivot **1138** in the direction indicated by the arrow **1132b**. Further, the outer tube **1144** may have a diameter D.sub.3 ranging from 5 mm to 10 mm, for example.

(354) FIG. **49** is a motor assembly **1160** that can be used with the surgical instrument **1100**, **1150** to drive the knife, according to one aspect of the present disclosure. The motor assembly **1160** comprises a motor **1162**, a planetary gear **1164**, a shaft **1166**, and a drive gear **1168**. The gear may be operably coupled to drive the knife bar **1145** (FIG. **46**). In one aspect, the drive gear **1168** or the shaft **1166** is operably coupled to a rotary drive mechanism **1170** described in connection with FIG. **50** to drive distal head rotation, articulation, and jaw closure.

(355) FIG. **50** is diagram of a motor drive circuit **1165**, according to one aspect of the present disclosure. The motor drive circuit **1165** is suitable for driving the motor M, which may be employed in the surgical instruments **1100**, **1150** described herein. The motor M is driven by an H-bridge comprising four switches S.sub.1-S.sub.4. The switches S.sub.1-S.sub.4 are generally solid state switches such as MOSFET switches. To turn the motor M in one direction, two switches S.sub.1, S.sub.4 are turned on and the other two switches S.sub.3, S.sub.2 are turned off. To reverse the direction of the motor M, the state of the switches S.sub.1-S.sub.4 is reversed such that the switches S.sub.1, S.sub.4 are turned off and the other two switches S.sub.3, S.sub.2 are turned on. Current sensing circuits can be placed in the motor drive circuit **1165** to sense motor currents i.sub.1a, i.sub.2a, i.sub.1b, i.sub.2b.

(356) FIG. **51** illustrates a rotary drive mechanism **1170** to drive distal head rotation, articulation, and jaw closure, according to one aspect of the present disclosure. The rotary drive mechanism **1170** has a primary rotary drive shaft **1172** that is operably coupled to the motor assembly **1160**. The primary rotary drive shaft **1172** is capable of being selectively coupled to at least two independent actuation mechanisms (first, second, both, neither) with a clutch mechanism located within the outer tube **1144** of the shaft assembly **1110**. The primary rotary drive shaft **1172** is coupled to independent clutches that allow the shaft functions to be independently coupled to the rotary drive shaft **1172**. For example, the articulation clutch **1174** is engaged to articulate the shaft assembly **1110** about the articulation axis **1175** of the articulation section **1130**. The distal head rotation clutch **1178** is engaged to rotate the distal rotation section **1134** and the jaw closure clutch **1179** is engaged to close the jaw members **1114a**, **1114b** of the end effector **1112**. The knife is advanced and retracted by the knife drive rod **1145**. All, none, or any combination of rotary

mechanisms can be couple at any one time.

(357) In one aspect, a micro-electrical clutching configuration enables rotation of the distal rotation section **1134** and articulation of the articulation section **1130** about pivot **1138** and articulation axis **1175**. In one aspect, a ferro-fluid clutch couples the clutch to the primary rotary drive shaft **1172** via a fluid pump. The clutch ferro-fluid is activated by electrical coils **1181**, **1183**, **1185** which are wrapped around the knife drive rod **1145**. The other ends of the coils **1181**, **1183**, **1185** are connected to three separate control circuits to independently actuate the clutches **1174**, **1178**, **1179**. In operation, when the coils **1181**, **1183**, **1185** are not energized, the clutches **1174**, **1178**, **1179** are disengaged and there is no articulation, rotation, or jaw movements.

(358) When the articulation clutch **1174** is engaged by energizing the coil **1181** and the distal head rotation clutch **1178** and the jaw closure clutch **1179** are disengaged by de-energizing the coils **1183**, **1185**, a gear **1180** is mechanically coupled to the primary rotary drive shaft **1172** to articulate the articulation section **1130**. In the illustrated orientation, when the primary rotary drive shaft **1172** rotates clockwise, the gear **1180** rotates clockwise and the shaft articulates in the right direction about the articulation axis **1175** and when the primary rotary drive shaft **1172** rotates counter clockwise, the gear **1180** rotates counter clockwise and the shaft articulates in the left direction about the articulation axis **1175**. It will be appreciated that left/right articulation depends on the orientation of the surgical instrument **1100**, **1150**.

(359) When the articulation clutch **1174** and the jaw closure clutch **1179** are disengaged by de-energizing the coils **1181**, **1185**, and the distal head rotation clutch **1178** is engaged by energizing the coil **1183**, the primary rotary drive shaft **1172** rotates the distal rotation section **1134** in the same direction of rotation. When the coil **1183** is energized, the distal head rotation clutch **1178** engages the primary rotary drive shaft **1172** with the distal rotation section **1134**. Accordingly, the distal rotation section **1134** rotates with the primary rotary drive shaft **1172**.

(360) When the articulation clutch **1174** and the distal head rotation clutch **1178** are disengaged by de-energizing the coils **1181**, **1183**, and the jaw closure clutch **1179** is engaged by energizing the coil **1185**, the jaw members **1114a**, **114b** can be opened or closed depending on the rotation of the primary rotary drive shaft **1172**. When the coil **1185** is energized, the jaw closure clutch **1179** engages a captive inner threaded drive member **1186**, which rotates in place in the direction of the primary rotary drive shaft **1172**. The captive inner threaded drive member **1186** includes outer threads that are in threaded engagement with an outer threaded drive member **1188**, which includes an inner threaded surface. As the primary rotary drive shaft **1172** rotates clockwise, the outer threaded drive member **1188** that is in threaded engagement with the captive inner threaded drive member **1186** will be driven in a proximal direction **1187** to close the jaw members **1114a**, **1114b**. As the primary rotary drive shaft **1172** rotates counterclockwise, the outer threaded drive member **1188** that is in threaded engagement with the captive inner threaded drive member **1186** will be driven in a distal direction **1189** to open the jaw members **1114a**, **1114b**.

(361) FIG. **52** is an enlarged, left perspective view of an end effector assembly with the jaw members shown in an open configuration, according to one aspect of the present disclosure. FIG. **53** is an enlarged, right side view of the end effector assembly of FIG. **52**, according to one aspect of the present disclosure. Referring now to FIGS. **52** and **53**, enlarged views of an end effector **1112** shown in an open position for approximating tissue. Jaw members **1114**, **1114b** are generally symmetrical and include similar component features which cooperate to permit facile rotation about pivot pin **1136** to effect the sealing and dividing of tissue. As a result and unless otherwise noted, only the jaw member **1114a** and the operative features associated therewith are describe in detail herein but as can be appreciated, many of these features apply to the other jaw member **1114b** as well.

(362) The jaw member **1114a** also includes a jaw housing **1115a**, an insulative substrate or insulator **1117a** and an electrically conductive surface **1116a**. The insulator **1117a** is configured to securely engage the electrically conductive sealing surface **1116a**. This may be accomplished by stamping,

by overmolding, by overmolding a stamped electrically conductive sealing plate and/or by overmolding a metal injection molded seal plate. These manufacturing techniques produce an electrode having an electrically conductive surface **1116a** that is surrounded by an insulator **1117a**. (363) As mentioned above, the jaw member **1114a** includes similar elements which include: a jaw housing **1115b**; insulator **1117b**; and an electrically conductive surface **1116b** that is dimensioned to securely engage the insulator **1117b**. Electrically conductive surface **1116b** and the insulator **1117b**, when assembled, form a longitudinally-oriented knife channel **1113** defined therethrough for reciprocation of the knife blade **1123**. The knife channel **1113** facilitates longitudinal reciprocation of the knife blade **1123** along a predetermined cutting plane to effectively and accurately separate the tissue along the formed tissue seal. Although not shown, the jaw member **1114a** may also include a knife channel that cooperates with the knife channel **1113** to facilitate translation of the knife through tissue.

(364) The jaw members **1114a**, **1114b** are electrically isolated from one another such that electrosurgical energy can be effectively transferred through the tissue to form a tissue seal. The electrically conductive surfaces **1116a**, **1116b** are also insulated from the remaining operative components of the end effector **1112** and the outer tube **1144**. A plurality of stop members may be employed to regulate the gap distance between the electrically conductive surfaces **1116a**, **1116b** to insure accurate, consistent, and reliable tissue seals.

(365) The structural and functional aspects of the battery assembly **1106** are similar to those of the battery assembly **106** for the surgical instrument **100** described in connection with FIGS. **1**, **2**, and **16-24**, including the battery circuits described in connection with FIGS. **20-24**. Accordingly, for conciseness and clarity of disclosure, such the structural and functional aspects of the battery assembly **106** are incorporated herein by reference and will not be repeated here. Furthermore, the structural and functional aspects of the RF generator circuits are similar to those of the RF generator circuits described in for the surgical instruments **500**, **600** described in connection with FIGS. **34-37**. Accordingly, for conciseness and clarity of disclosure, such the structural and functional aspects of the RF generator circuits are incorporated herein by reference and will not be repeated here. Furthermore, the surgical instrument **1100** includes the battery and control circuits described in connection with FIGS. **12-15**, including, for example, the control circuit **210** described in connection with FIG. **14** and the electrical circuit **300** described in connection with FIG. **15**. Accordingly, for conciseness and clarity of disclosure, the description of the circuits described in connection with FIGS. **12-15** is incorporated herein by reference and will not be repeated here.

(366) For a more detailed description of an electrosurgical instrument comprising a cutting mechanism and an articulation section that is operable to deflect the end effector away from the longitudinal axis of the shaft, reference is made to U.S. Pat. Nos. 9,028,478 and 9,113,907, each of which is herein incorporated by reference.

(367) FIG. **54** illustrates a modular battery powered handheld electrosurgical instrument **1200** with distal articulation, according to one aspect of the present disclosure. The surgical instrument **1200** comprises a handle assembly **1202**, a knife drive assembly **1204**, a battery assembly **1206**, a shaft assembly **1210**, and an end effector **1212**. The end effector **1212** comprises a pair of jaw members **1214a**, **1214b** in opposing relationship affixed to a distal end thereof. The end effector **1212** is configured to articulate and rotate. FIG. **55** is an exploded view of the surgical instrument **1200** shown in FIG. **54**, according to one aspect of the present disclosure. The end effector **1212** for use with the surgical instrument **1200** for sealing and cutting tissue includes a pair of jaw members **1214a**, **1214b** in opposing relationship movable relative to each other to grasp tissue therebetween. Either jaw member **1214a**, **1214b** may include a jaw housing and an electrically conductive surface **1216a**, **1216b**, e.g., electrodes, adapted to connect to a source of electrosurgical energy (RF source) such that the electrically conductive surfaces are capable of conducting electrosurgical energy through tissue held therebetween to effect a tissue seal. The jaw members **1214a**, **1214b** and the electrically conductive surfaces **1216a**, **1216b** include a channel defined therein and extending

along a length thereof that communicates with a knife drive rod **1245** connected to a knife drive assembly **1204**. The knife **1274** (FIGS. **60-61**) is configured to translate and reciprocate along the channels to cut tissue grasped between the jaw members **1214a**, **1214b**. The knife has an I-beam configuration such that the jaw members **1214a**, **1214b** are brought closer together as the knife **1274** advances through the channels. In one aspect, the electrically conductive surfaces **1216a**, **1216b** are offset relative to each other. The knife **1274** includes a sharp distal end.

(368) The handle assembly **1202** of the surgical instrument shown in FIGS. **54-55** comprises a motor assembly **1260** and a knife drive assembly **1204**. In one aspect, a display assembly may be provided on the housing **1248**. The display assembly may comprise a display, such as an LCD display, for example, which is removably connectable to a housing **1248** portion of the handle assembly **1202**. The LCD display provides a visual display of surgical procedure parameters such as tissue thickness, status of seal, status of cut, tissue thickness, tissue impedance, algorithm being executed, battery capacity, among other parameters. With reference now to FIGS. **54-55**, the surgical instrument **1200** is configured to use high-frequency (RF) current and a knife **1274** (FIGS. **60-61**) to carry out surgical coagulation/cutting treatments on living tissue, and uses high-frequency current to carry out a surgical coagulation treatment on living tissue. The high-frequency (RF) current can be applied independently or in combination with algorithms or user input control. The knife drive assembly **1204**, battery assembly **1206**, and shaft assembly **1210** are modular components that are removably connectable to the handle assembly **1202**. A motor assembly **1240** may be located within the handle assembly **1202**. The RF generator and motor drive circuits are described in connection with FIGS. **34-37** and **50**, for example, are located within the housing **1248**. The housing **1248** includes a removable cover plate **1276** to provide access to the circuits and mechanisms located within the housing **1248**. The knife drive assembly **1204** includes gears and linkages operably coupled to the handle assembly **1202** and the switch section **1220** to activate and drive the knife **1274**. As discussed in more detail hereinbelow, the knife **1274** has an I-beam configuration.

(369) The shaft assembly **1210** comprises an outer tube **1244**, a knife drive rod **1245**, and an inner tube (not shown). The shaft assembly **1210** comprises an articulation section **1230**. The end effector **1212** comprises a pair of jaw members **1214a**, **1214b** and a knife **1274** configured to reciprocate with channels formed in the jaw members **1214a**, **1214b**. In one aspect, the knife **1274** may be driven by a motor. The jaw member **1214a**, **1214b** comprises an electrically conductive surface **1216a**, **1216b** coupled to the RF generator circuit for delivering high-frequency current to tissue grasped between the jaw members **1214a**, **1214b**. The jaw members **1214a**, **1214b** are pivotally rotatable about a pivot pin **1235** to grasp tissue between the jaw members **1214a**, **1214b**. The jaw members **1214a**, **1214b** are operably coupled to a trigger **1208** such that when the trigger **1208** is squeezed one or both of the jaw members **1214a**, **1214b** close to grasp tissue and when the trigger **1208** is released the jaw members **1214a**, **1214b** open to release tissue. In the illustrated example, one jaw member **1214a** is movable relative to the other jaw member **1214b**. In other aspects, both jaw members **1214a**, **1214b** may be movable relative to each other. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the trigger **1208** to measure the force applied to the trigger **1208** by the user. In another aspect, force sensors such as strain gages or pressure sensors may be coupled to the switch section **1220** first and second switch **1221a**, **1221b** buttons such that displacement intensity corresponds to the force applied by the user to the switch section **1220** first and second switch **1221a**, **1221b** buttons.

(370) The jaw member **1214a** is operably coupled to a trigger **1208** such that when the trigger **1208** is squeezed the jaw member **1214a** closes to grasp tissue and when the trigger **1208** is released the jaw member **1214a** opens to release tissue. In a one-stage trigger configuration, the trigger **1208** is squeezed to close the jaw member **1214a** and, once the jaw member **1214a** is closed, a first switch **1221a** of a switch section **1220** is activated to energize the RF generator to seal the tissue. After the tissue is sealed, a second switch **1221b** of the switch section **1220** is activated to advance a knife to

cut the tissue. In various aspects, the trigger **1208** may be a two-stage, or a multi-stage, trigger. In a two-stage trigger configuration, during the first stage, the trigger **1208** is squeezed part of the way to close the jaw member **1214a** and during the second stage, the trigger **1208** is squeezed the rest of the way to energize the RF generator circuit to seal the tissue. After the tissue is sealed, one of the switches **1221a**, **1221b** can be activated to advance the knife to cut the tissue. After the tissue is cut, the jaw member **1214a** is opened by releasing the trigger **1208** to release the tissue.

(371) The shaft assembly **1210** includes an articulation section **1230** that is operable to deflect the end effector **1212** away from the longitudinal axis “A” of the shaft assembly **1210**. The dials **1232a**, **1232b** are operable to pivot the articulation section **1230** at the distal end of the elongated shaft assembly **1210** to various articulated orientations with respect to the longitudinal axis A-A. More particularly, the articulation dials **1232a**, **1232b** operably couple to a plurality of cables or tendons that are in operative communication with the articulation section **1230** of the shaft assembly **1210**, as described in greater detail below. One articulation dial **1232a** may be rotated in the direction of arrows “C0” to induce pivotal movement in a first plane, e.g., a vertical plane, as indicated by arrows “C1”. Similarly, another articulation dial **1232b** may be rotated in the direction of arrows “D0” to induce pivotal movement in a second plane, e.g., a horizontal plane, as indicated by arrows “D1”. Rotation of the articulation dials **1232a**, **1232b** in either direction of arrows “C0” or “D0” results in the tendons pivoting or articulating the shaft assembly **1210** about the articulation section **1230**.

(372) The battery assembly **1206** is electrically connected to the handle assembly **1202** by an electrical connector **1231**. The handle assembly **1202** is provided with a switch section **1220**. A first switch **1221a** and a second switch **1221b** are provided in the switch section **1220**. The RF generator is energized by actuating the first switch **1221a** and the knife **1274** may be activated by energizing the motor assembly **1240** by actuating the second switch **1221b**. Accordingly, the first switch **1221a** energizes the RF circuit to drive the high-frequency current through the tissue to form a seal and the second switch **1221b** energizes the motor to drive the knife **1274** to cut the tissue. In other aspects, the knife **1274** may be fired manually using a two-stage trigger **1208** configuration. The structural and functional aspects of the battery assembly **1206** are similar to those of the battery assembly **106** for the surgical instrument **100** described in connection with FIGS. 1, 2, and 16-24. Accordingly, for conciseness and clarity of disclosure, such the structural and functional aspects of the battery assembly **106** are incorporated herein by reference and will not be repeated here.

(373) A rotation knob **1218** is operably coupled to the shaft assembly **1210**. Rotation of the rotation knob **1218** $\pm 360^\circ$ in the direction indicated by the arrows **1226** causes the outer tube **1244** to rotate $\pm 360^\circ$ in the respective direction of the arrows **1228**. The end effector **1212** may be articulated by way of control buttons such that actuation of control buttons articulates the end effector **1212** in one direction indicated by arrows C1 and D1. Further, the outer tube **1244** may have a diameter D.sub.3 ranging from 5 mm to 10 mm, for example.

(374) FIG. 56 is an enlarged area detail view of an articulation section illustrated in FIG. 54 including electrical connections, according to one aspect of the present disclosure. FIG. 57 is an enlarged area detail view articulation section illustrated in FIG. 56 including electrical connections, according to one aspect of the present disclosure. With reference now to FIGS. 56-57, there is shown the articulation section **1230** is operably disposed on or coupled to the shaft assembly **1210** between the proximal end and the distal end **1222**, respectively. In the aspect illustrated in FIGS. 56-57, the articulation section **1230** is defined by a plurality of articulating links **1233** (links **1233**). The links **1233** are configured to articulate the shaft assembly **1210** transversely across the longitudinal axis “A-A” in either a horizontal or vertical plane, see FIG. 54. For illustrative purposes, the shaft assembly **1210** is shown articulated across the horizontal plane.

(375) The links **1233** collectively define a central annulus **1238** therethrough that is configured to receive a drive mechanism, e.g., a drive rod, therethrough. As can be appreciated, the configuration of the central annulus **1238** provides adequate clearance for the drive rod therethrough. The central

annulus **1238** defines an axis “B-B” therethrough that is parallel to the longitudinal axis “A-A” when the shaft assembly **1210** is in a non-articulated configuration, see FIG. **54**.

(376) Continuing with reference to FIGS. **56-57**, the links **1233** are operably coupled to the articulation dials **1232a**, **1232b** via tendons **1234**. For illustrative purposes, four (4) tendons **1234** are shown. The tendons **1234** may be constructed of stainless steel wire or other material suitable for transmitting tensile forces to a distal-most link of links **1233**. Regardless of the construction materials, the tendons **1234** exhibit a spring rate that is amplified over the length of the tendons **1234** and thus, the tendons **1234** may tend to stretch when external loads are applied to the elongated shaft assembly **1210**. This tendency to stretch may be associated with an unintended change in orientation of the distal end **1222** of the elongated shaft assembly **1210**, e.g., without a corresponding movement of the articulation dials **1232a**, **1232b** initiated by the surgeon.

(377) The tendons **1234** operably couple to the articulating dials **1232a**, **1232b** that are configured to actuate the tendons **1234**, e.g., “pull” the tendons **1234**, when the articulating dials **1232a**, **1232b** are rotated. The plurality of tendons **1234** operably couple to the links **1233** via one or more suitable coupling methods. More particularly, the link **1233** includes a corresponding plurality of first apertures or bores **1236a** defined therein (four (4) bores **1236a** are shown in the representative figures) that are radially disposed along the links **1233** and centrally aligned along a common axis, see FIG. **56**. A bore of the plurality of bores **1236a** is configured to receive a tendon **1234**. A distal end of a tendon **1234** is operably coupled to a distal most link of the links **1233** by suitable methods, e.g., one or more of the coupling methods described above.

(378) Continuing with reference to FIGS. **56-57** a link **1233** includes a second plurality of bores **1236b** (four (4) bores **1236b** are shown in the representative drawings, as best seen in FIG. **56**). A bore **1236b** is configured to receive a corresponding conductive lead of a plurality of conductive leads **1237** (four (4) conductive leads **1237** are shown in the representative drawings). The conductive leads **1237** are configured to transition between first and second states within the second plurality of bores **1236b**. To facilitate transitioning of the conductive leads **1237**, a bore **1236b** includes a diameter that is greater than a diameter of the conductive leads **1237** when the conductive leads **1237** are in the first state.

(379) The surgical instrument **1220** includes electrical circuitry that is configured to selectively induce a voltage and current flow to the plurality of conductive leads **1237** such that a conductive lead **1237** transitions from the first state to the second state. To this end, the generator G provides a voltage potential Eo of suitable proportion. A voltage is induced in a conductive lead **1237** and current flow therethrough. The current flowing through a conductive lead **1237** causes the conductive lead **1237** to transition from the first state (FIG. **56**) to the second state (FIG. **57**). In the second state, the conductive lead **1237** provides an interference fit between the conductive lead **1237** and the corresponding bores **1236b**, as best seen in FIG. **57**.

(380) FIG. **58** illustrates a perspective view of components of the shaft assembly **1210**, end effector **1212**, and cutting member **1254** of the surgical instrument **1200** of FIG. **54**, according to one aspect of the present disclosure. FIG. **59** illustrates the articulation section in a second stage of articulation, according to one aspect of the present disclosure. With reference now to FIGS. **58-59**, one articulation band **1256a** is slidably disposed in one side recess of a separator **1261** while a second articulation band **1256b** (FIG. **59**) is slidably disposed in the other side recess of the separator **1261**. A cutting member driver tube is movable longitudinally to drive a driver block **1258** longitudinally, to thereby move cutting member **1254** longitudinally. The side recesses include longitudinally extending grooves that are configured to reduce the contact surface area with articulation bands **1256a**, **1256b**, thereby reducing friction between separator **1261** and articulation bands **1256a**, **1256b**. The separator **1261** also may be formed of a low friction material and/or include a surface treatment to reduce friction. Articulation bands **1256a**, **1256b** extend longitudinally along the length of the shaft assembly **1210**, including through the articulation section **1230**. The distal end **1252** of one articulation band **1256a** is secured to one side of the

proximal portion **1250** of end effector **1212** at an anchor point. The distal end **1262** of the second articulation band **1256b** is secured to the other side of proximal portion **1250** of end effector **1212** at an anchor point. A rotary articulation knob is operable to selectively advance the articulation band **1256a** distally while simultaneously retracting the second articulation band **1256b** proximally, and vice-versa. It should be understood that this opposing translation will cause articulation section **1230** to bend, thereby articulating end effector **1212**. In particular, the end effector **1212** will deflect toward whichever articulation band **1256a**, **1256b** is being retracted proximally; and away from whichever articulation band **1256a**, **1256b** is being advanced distally.

(381) With continued referenced to FIGS. **58-59**, several of the above described components are shown interacting to bend the articulation section **1230** to articulate end effector **1212**. In FIG. **58**, articulation **1230** is in a straight configuration. Then, one of the articulation dials **1232a**, **1232b** (FIGS. **54-55**) is rotated, which causes a lead screw to translate proximally and another lead screw to advance distally. This proximal translation of one lead screw pulls the articulation band **1256b** proximally, which causes articulation section **1230** to start bending as shown in FIG. **59**. This bending of articulation section **1230** pulls the other articulation band **1256a** distally. The distal advancement of lead screw in response to rotation of the articulation dials **1232a**, **1232b** enables the articulation band **1256a** and the drive member to advance distally. In some other versions, the distal advancement of the lead screw actively drives drive member and articulation band **1256a** distally. As the user continues rotating one of the articulation dials **1232a**, **1232b**, the above described interactions continue in the same fashion, resulting in further bending of articulation section **1230** as shown in FIG. **59**. It should be understood that rotating the articulation dials **1232a**, **1232b** in the opposite direction will cause articulation section **1230** to straighten, and further rotation in the opposite direction will cause articulation section **1230** to bend in the opposite direction.

(382) FIG. **60** illustrates a perspective view of the end effector **1212** of the device of FIGS. **54-59** in an open configuration, according to one aspect of the present disclosure. The end effector **1212** of the present example comprises a pair of jaw members **1214a**, **1214b**. In the present example, one jaw member **1214b** is fixed relative to shaft assembly; while the other jaw member **1214a** pivots relative to shaft assembly, toward and away from the other jaw member **1214b**. In some versions, actuators such as rods or cables, etc., may extend through a sheath and be joined with one jaw member **1214a** at a pivotal coupling, such that longitudinal movement of the actuator rods/cables/etc. through the shaft assembly provides pivoting of the jaw member **1214a** relative to shaft assembly and relative to the second jaw member **1214b**. Of course, the jaw members **1214a**, **1214b** instead may have any other suitable kind of movement and may be actuated in any other suitable fashion. By way of example only, the jaw members **1214a**, **1214b** may be actuated and thus closed by longitudinal translation of a firing beam **1266**, such that actuator rods/cables/etc. may simply be eliminated in some versions. The upper side of one jaw member **1214a** including a plurality of teeth serrations **1272**. It should be understood that the lower side of the other jaw member **1214b** may include complementary serrations **1277** that nest with the serrations **1272**, to enhance gripping of tissue captured between the jaw members **1214a**, **1214b** of the end effector **1212** without necessarily tearing the tissue.

(383) FIG. **61** illustrates a cross-sectional end view of the end effector **1212** of FIG. **60** in a closed configuration and with the blade **1274** in a distal position, according to one aspect to the present disclosure. With reference now to FIGS. **60-61**, one jaw member **1214a** defines a longitudinally extending elongate slot **1268**; while the other jaw member **1214b** also defines a longitudinally extending elongate slot **1270**. In addition, the underside of one jaw member **1214a** presents an electrically conductive surface **1216a**; while the top side of the other jaw member **1214b** presents another electrically conductive surface **1216b**. The electrically conductive surfaces **1216a**, **1216b** are in communication with an electrical source **1278** and a controller **1280** via one or more conductors (not shown) that extend along the length of shaft assembly. The electrical source **1278**

is operable to deliver RF energy to first electrically conductive surface **1216a** at a first polarity and to second electrically conductive surface **1216b** at a second (opposite) polarity, such that RF current flows between electrically conductive surfaces **1216a**, **1216b** and thereby through tissue captured between the jaw members **1214a**, **1214b**. In some versions, firing beam **1266** serves as an electrical conductor that cooperates with the electrically conductive surfaces **1216a**, **1216b** (e.g., as a ground return) for delivery of bipolar RF energy captured between the jaw members **1214a**, **1214b**. The electrical source **1278** may be external to surgical instrument **1200** or may be integral with surgical instrument **1200** (e.g., in the handle assembly **1202**, etc.), as described in one or more references cited herein or otherwise. A controller **1280** regulates delivery of power from electrical source **1278** to the electrically conductive surfaces **1216a**, **1216b**. The controller **1280** may also be external to surgical instrument **1200** or may be integral with surgical instrument **1200** (e.g., in handle assembly **1202**, etc.), as described in one or more references cited herein or otherwise. It should also be understood that the electrically conductive surfaces **1216a**, **1216b** may be provided in a variety of alternative locations, configurations, and relationships.

(384) Still with reference to FIGS. **60-61**, the surgical instrument **1200** of the present example includes a firing beam **1266** that is longitudinally movable along part of the length of end effector **1212**. The firing beam **1266** is coaxially positioned within the shaft assembly **1210**, extends along the length of the shaft assembly **1210**, and translates longitudinally within the shaft assembly **1210** (including the articulation section **1230** in the present example), though it should be understood that firing beam **1266** and the shaft assembly **1210** may have any other suitable relationship. The firing beam **1266** includes a knife **1274** with a sharp distal end, an upper flange **1281**, and a lower flange **1282**. As best seen in FIG. **61**, the knife **1274** extends through slots **1268**, **1270** of the jaw members **1214a**, **1214b**, with the upper flange **1281** being located above the jaw member **1214a** in a recess **1284** and the lower flange **1282** being located below the jaw member **1214b** in a recess **1286**. The configuration of the knife **1274** and the flanges **1281**, **1282** provides an “I-beam” type of cross section at the distal end of firing beam **1266**. While the flanges **1281**, **1282** extend longitudinally only along a small portion of the length of firing beam **1266** in the present example, it should be understood that the flanges **1281**, **1282** may extend longitudinally along any suitable length of firing beam **1266**. In addition, while the flanges **1281**, **1282** are positioned along the exterior of the jaw members **1214a**, **1214b**, the flanges **1281**, **1282** may alternatively be disposed in corresponding slots formed within jaw members **1214a**, **1214b**. For instance, the jaw members **1214a**, **1214b** may define a “T”-shaped slot, with parts of the knife **1274** being disposed in one vertical portion of a “T”-shaped slot and with the flanges **1281**, **1282** being disposed in the horizontal portions of the “T”-shaped slots. Various other suitable configurations and relationships will be apparent to those of ordinary skill in the art in view of the teachings herein. By way of example only, the end effector **1212** may include one or more positive temperature coefficient (PTC) thermistor bodies **1288**, **1290** (e.g., PTC polymer, etc.), located adjacent to the electrically conductive surfaces **1216a**, **1216b** and/or elsewhere.

(385) The structural and functional aspects of the battery assembly **1206** are similar to those of the battery assembly **106** for the surgical instrument **100** described in connection with FIGS. **1**, **2**, and **16-24**, including the battery circuits described in connection with FIGS. **20-24**. Accordingly, for conciseness and clarity of disclosure, such the structural and functional aspects of the battery assembly **106** are incorporated herein by reference and will not be repeated here. Furthermore, the structural and functional aspects of the RF generator circuits are similar to those of the RF generator circuits described in for the surgical instruments **500**, **600** described in connection with FIGS. **34-37**. Accordingly, for conciseness and clarity of disclosure, such the structural and functional aspects of the RF generator circuits are incorporated herein by reference and will not be repeated here. Furthermore, the surgical instrument **1200** includes the battery and control circuits described in connection with FIGS. **12-15**, including, for example, the control circuit **210** described in connection with FIG. **14** and the electrical circuit **300** described in connection with FIG. **15**.

Accordingly, for conciseness and clarity of disclosure, the description of the circuits described in connection with FIGS. **12-15** is incorporated herein by reference and will not be repeated here.

(386) For a more detailed description of an electrosurgical instrument comprising a cutting mechanism and an articulation section that is operable to deflect the end effector away from the longitudinal axis of the shaft, reference is made to U.S. Patent Application Publication No. 2013/0023868, now U.S. Pat. No. 9,545,253, which is herein incorporated by reference.

(387) It should also be understood that any of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein may be modified to include a motor or other electrically powered device to drive an otherwise manually moved component. Various examples of such modifications are described in U.S. Patent Application Publication No. 2012/0116379, now U.S. Pat. No. 9,161,803, and U.S. Patent Application Publication No. 2016/0256184, now U.S. Pat. No. 9,808,246, each of which is incorporated herein by reference. Various other suitable ways in which a motor or other electrically powered device may be incorporated into any of the devices herein will be apparent to those of ordinary skill in the art in view of the teachings herein.

(388) It should also be understood that the circuits described in connection with FIGS. **11-15, 20-24, 34-37, and 50** may be configured to operate either alone or in combination with any of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein.

(389) FIGS. **62-70** describe various circuits that are configured to operate with any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described in connections with FIGS. **1-61**. Turning now to FIG. **62**, there is shown the components of a control circuit **1300** of the surgical instrument, according to one aspect of the present disclosure. The control circuit **1300** comprises a processor **1302** coupled to a volatile memory **1304**, one or more sensors **1306**, a nonvolatile memory **1308** and a battery **1310**. In one aspect, the surgical instrument may comprise a handle housing to house the control circuit **1300** and to contain general purpose controls to implement the power conservation mode. In some aspects, the processor **1302** may be a primary processor of the surgical instrument that includes one or more secondary processors. In some aspects, the processor **1302** may be stored within the battery **1310**. The processor **1302** is configured to control various operations and functions of the surgical instrument by executing machine executable instructions, such as control programs or other software modules. For example, execution of an energy modality control program by the processor **1302** enables selection of a particular type of energy to be applied to patient tissue by a surgeon using the surgical instrument. The surgical instrument may comprise an energy modality actuator located on the handle of the surgical instrument. The actuator may be a slider, a toggle switch, a segmented momentary contact switch, or some other type of actuator. Actuation of the energy modality actuator causes the processor **1302** to activate an energy modality corresponding to a selected type of energy. The type of energy can be ultrasonic, RF, or a combination of ultrasonic and RF energy. In various aspects general, the processor **1302** is electrically coupled to the plurality of circuit segments of the surgical instrument as illustrated in FIG. **63** to activate or deactivate the circuit segments in accordance with energization and deenergization sequences.

(390) The volatile memory **1304**, such as a random-access memory (RAM), temporarily stores selected control programs or other software modules while the processor **1302** is in operation, such as when the processor **1302** executes a control program or software module. The one or more sensors **1306** may include force sensors, temperature sensors, current sensors or motion sensors. In some aspects, the one or more sensors **1306** may be located at the shaft, end effector, battery, or handle, or any combination or sub-combination thereof. The one or more sensors **1306** transmit data associated with the operation of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described in connection with FIGS. **1-61**, such as the presence of tissue grasped by the jaws of the end effector or the force applied by the motor. In one aspect, the one or more sensors **1306** may include an accelerometer to verify the function or operation of the circuit segments, based on a safety check and a Power On Self Test (POST). Machine executable instructions such as

control programs or other software modules are stored in the nonvolatile memory **1308**. For example, the nonvolatile memory **1308** stores the Basic Input/Output System (BIOS) program. The nonvolatile memory **1308** may be a read-only memory, erasable programmable ROM (EPROM), an EEPROM, flash memory or some other type of nonvolatile memory device. Various examples of control programs are described in U.S. Patent Application Publication No. 2015/0272578, now U.S. Pat. No. 9,690,362, which is incorporated herein by reference in its entirety. The battery **1310** powers the surgical instrument by providing a source voltage that causes a current. The battery **1310** may comprise the motor control circuit segment **1428** illustrated in FIG. **63**.

(391) In one aspect, the processor **1302** may be any single core or multicore processor such as those known under the trade name ARM Cortex by Texas Instruments. In one aspect, the processor **1302** may be implemented as a safety processor comprising two microcontroller-based families such as TMS570 and RM4x known under the trade name Hercules ARM Cortex R4, also by Texas Instruments. Nevertheless, other suitable substitutes for microcontrollers and safety processor may be employed, without limitation. In one aspect, the safety processor may be configured specifically for IEC 61508 and ISO 26262 safety critical applications, among others, to provide advanced integrated safety features while delivering scalable performance, connectivity, and memory options.

(392) In certain aspects, the processor **1302** may be an LM 4F230H5QR, available from Texas Instruments, for example. In at least one example, the Texas Instruments LM4F230H5QR is an ARM Cortex-M4F Processor Core comprising on-chip memory of 256 KB single-cycle flash memory, or other non-volatile memory, up to 40 MHZ, a prefetch buffer to improve performance above 40 MHZ, a 32 KB single-cycle serial random access memory (SRAM), internal read-only memory (ROM) loaded with StellarisWare® software, 2 KB electrically erasable programmable read-only memory (EEPROM), one or more pulse width modulation (PWM) modules, one or more quadrature encoder inputs (QED analog, one or more 12-bit Analog-to-Digital Converters (ADC) with 12 analog input channels, among other features that are readily available for the product datasheet. Other processors may be readily substituted and, accordingly, the present disclosure should not be limited in this context.

(393) FIG. **63** is a system diagram **1400** of a segmented circuit **1401** comprising a plurality of independently operated circuit segments **1402**, **1414**, **1416**, **1420**, **1424**, **1428**, **1434**, **1440**, according to one aspect of the present disclosure. A circuit segment of the plurality of circuit segments of the segmented circuit **1401** comprises one or more circuits and one or more sets of machine executable instructions stored in one or more memory devices. The one or more circuits of a circuit segment are coupled to for electrical communication through one or more wired or wireless connection media. The plurality of circuit segments are configured to transition between three modes comprising a sleep mode, a standby mode and an operational mode.

(394) In one aspect shown, the plurality of circuit segments **1402**, **1414**, **1416**, **1420**, **1424**, **1428**, **1434**, **1440** start first in the standby mode, transition second to the sleep mode, and transition third to the operational mode. However, in other aspects, the plurality of circuit segments may transition from any one of the three modes to any other one of the three modes. For example, the plurality of circuit segments may transition directly from the standby mode to the operational mode. Individual circuit segments may be placed in a particular state by the voltage control circuit **1408** based on the execution by the processor **1302** of machine executable instructions. The states comprise a deenergized state, a low energy state, and an energized state. The deenergized state corresponds to the sleep mode, the low energy state corresponds to the standby mode, and the energized state corresponds to the operational mode. Transition to the low energy state may be achieved by, for example, the use of a potentiometer.

(395) In one aspect, the plurality of circuit segments **1402**, **1414**, **1416**, **1420**, **1424**, **1428**, **1434**, **1440** may transition from the sleep mode or the standby mode to the operational mode in accordance with an energization sequence. The plurality of circuit segments also may transition

from the operational mode to the standby mode or the sleep mode in accordance with a deenergization sequence. The energization sequence and the deenergization sequence may be different. In some aspects, the energization sequence comprises energizing only a subset of circuit segments of the plurality of circuit segments. In some aspects, the deenergization sequence comprises deenergizing only a subset of circuit segments of the plurality of circuit segments.

(396) Referring back to the system diagram **1400** in FIG. **63**, the segmented circuit **1401** comprise a plurality of circuit segments comprising a transition circuit segment **1402**, a processor circuit segment **1414**, a handle circuit segment **1416**, a communication circuit segment **1420**, a display circuit segment **1424**, a motor control circuit segment **1428**, an energy treatment circuit segment **1434**, and a shaft circuit segment **1440**. The transition circuit segment comprises a wake up circuit **1404**, a boost current circuit **1406**, a voltage control circuit **1408**, a safety controller **1410** and a POST controller **1412**. The transition circuit segment **1402** is configured to implement a deenergization and an energization sequence, a safety detection protocol, and a POST.

(397) In some aspects, the wake up circuit **1404** comprises an accelerometer button sensor **1405**. In aspects, the transition circuit segment **1402** is configured to be in an energized state while other circuit segments of the plurality of circuit segments of the segmented circuit **1401** are configured to be in a low energy state, a deenergized state or an energized state. The accelerometer button sensor **1405** may monitor movement or acceleration of any one of the surgical instruments **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-61**. For example, the movement may be a change in orientation or rotation of the surgical instrument. The surgical instrument may be moved in any direction relative to a three dimensional Euclidean space by for example, a user of the surgical instrument. When the accelerometer button sensor **1405** senses movement or acceleration, the accelerometer button sensor **1405** sends a signal to the voltage control circuit **1408** to cause the voltage control circuit **1408** to apply voltage to the processor circuit segment **1414** to transition the processor **1302** and the volatile memory **1304** to an energized state. In aspects, the processor **1302** and the volatile memory **1304** are in an energized state before the voltage control circuit **1409** applies voltage to the processor **1302** and the volatile memory **1304**. In the operational mode, the processor **1302** may initiate an energization sequence or a deenergization sequence. In various aspects, the accelerometer button sensor **1405** may also send a signal to the processor **1302** to cause the processor **1302** to initiate an energization sequence or a deenergization sequence. In some aspects, the processor **1302** initiates an energization sequence when the majority of individual circuit segments are in a low energy state or a deenergized state. In other aspects, the processor **1302** initiates a deenergization sequence when the majority of individual circuit segments are in an energized state.

(398) Additionally or alternatively, the accelerometer button sensor **1405** may sense external movement within a predetermined vicinity of the surgical instrument. For example, the accelerometer button sensor **1405** may sense a user of any one of the surgical instruments **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-61** moving a hand of the user within the predetermined vicinity. When the accelerometer button sensor **1405** senses this external movement, the accelerometer button sensor **1405** may send a signal to the voltage control circuit **1408** and a signal to the processor **1302**, as previously described. After receiving the sent signal, the processor **1302** may initiate an energization sequence or a deenergization sequence to transition one or more circuit segments between the three modes. In aspects, the signal sent to the voltage control circuit **1408** is sent to verify that the processor **1302** is in operational mode. In some aspects, the accelerometer button sensor **1405** may sense when the surgical instrument has been dropped and send a signal to the processor **1302** based on the sensed drop. For example, the signal can indicate an error in the operation of an individual circuit segment. The one or more sensors **1306** may sense damage or malfunctioning of the affected individual circuit segments. Based on the sensed damage or malfunctioning, the POST controller **1412** may perform a POST of the corresponding individual circuit segments.

(399) An energization sequence or a deenergization sequence may be defined based on the accelerometer button sensor **1405**. For example, the accelerometer button sensor **1405** may sense a particular motion or a sequence of motions that indicates the selection of a particular circuit segment of the plurality of circuit segments. Based on the sensed motion or series of sensed motions, the accelerometer button sensor **1405** may transmit a signal comprising an indication of one or more circuit segments of the plurality of circuit segments to the processor **1302** when the processor **1302** is in an energized state. Based on the signal, the processor **1302** determines an energization sequence comprising the selected one or more circuit segments. Additionally or alternatively, a user of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61** may select a number and order of circuit segments to define an energization sequence or a deenergization sequence based on interaction with a graphical user interface (GUI) of the surgical instrument.

(400) In various aspects, the accelerometer button sensor **1405** may send a signal to the voltage control circuit **1408** and a signal to the processor **1302** only when the accelerometer button sensor **1405** detects movement of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61** or external movement within a predetermined vicinity above a predetermined threshold. For example, a signal may only be sent if movement is sensed for 5 or more seconds or if the surgical instrument is moved 5 or more inches. In other aspects, the accelerometer button sensor **1405** may send a signal to the voltage control circuit **1408** and a signal to the processor **1302** only when the accelerometer button sensor **1405** detects oscillating movement of the surgical instrument. A predetermined threshold reduces inadvertent transition of circuit segments of the surgical instrument. As previously described, the transition may comprise a transition to operational mode according to an energization sequence, a transition to low energy mode according to a deenergization sequence, or a transition to sleep mode according to a deenergization sequence. In some aspects, the surgical instrument comprises an actuator that may be actuated by a user of the surgical instrument. The actuation is sensed by the accelerometer button sensor **1405**. The actuator may be a slider, a toggle switch, or a momentary contact switch. Based on the sensed actuation, the accelerometer button sensor **1405** may send a signal to the voltage control circuit **1408** and a signal to the processor **1302**.

(401) The boost current circuit **1406** is coupled to the battery **1310**. The boost current circuit **1406** is a current amplifier, such as a relay or transistor, and is configured to amplify the magnitude of a current of an individual circuit segment. The initial magnitude of the current corresponds to the source voltage provided by the battery **1310** to the segmented circuit **1401**. Suitable relays include solenoids. Suitable transistors include field-effect transistors (FET), MOSFET, and bipolar junction transistors (BJT). The boost current circuit **1406** may amplify the magnitude of the current corresponding to an individual circuit segment or circuit which requires more current draw during operation of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described in connection with FIGS. **1-61**. For example, an increase in current to the motor control circuit segment **1428** may be provided when a motor of the surgical instrument requires more input power. The increase in current provided to an individual circuit segment may cause a corresponding decrease in current of another circuit segment or circuit segments. Additionally or alternatively, the increase in current may correspond to voltage provided by an additional voltage source operating in conjunction with the battery **1310**.

(402) The voltage control circuit **1408** is coupled to the battery **1310**. The voltage control circuit **1408** is configured to provide voltage to or remove voltage from the plurality of circuit segments. The voltage control circuit **1408** is also configured to increase or reduce voltage provided to the plurality of circuit segments of the segmented circuit **1401**. In various aspects, the voltage control circuit **1408** comprises a combinational logic circuit such as a multiplexer (MUX) to select inputs, a plurality of electronic switches, and a plurality of voltage converters. An electronic switch of the plurality of electronic switches may be configured to switch between an open and closed

configuration to disconnect or connect an individual circuit segment to or from the battery **1310**. The plurality of electronic switches may be solid state devices such as transistors or other types of switches such as wireless switches, ultrasonic switches, accelerometers, inertial sensors, among others. The combinational logic circuit is configured to select an individual electronic switch for switching to an open configuration to enable application of voltage to the corresponding circuit segment. The combination logic circuit also is configured to select an individual electronic switch for switching to a closed configuration to enable removal of voltage from the corresponding circuit segment. By selecting a plurality of individual electronic switches, the combination logic circuit may implement a deenergization sequence or an energization sequence. The plurality of voltage converters may provide a stepped-up voltage or a stepped-down voltage to the plurality of circuit segments. The voltage control circuit **1408** may also comprise a microprocessor and memory device, as illustrated in FIG. 62.

(403) The safety controller **1410** is configured to perform safety checks for the circuit segments. In some aspects, the safety controller **1410** performs the safety checks when one or more individual circuit segments are in the operational mode. The safety checks may be performed to determine whether there are any errors or defects in the functioning or operation of the circuit segments. The safety controller **1410** may monitor one or more parameters of the plurality of circuit segments. The safety controller **1410** may verify the identity and operation of the plurality of circuit segments by comparing the one or more parameters with predefined parameters. For example, if an RF energy modality is selected, the safety controller **1410** may verify that an articulation parameter of the shaft matches a predefined articulation parameter to verify the operation of the RF energy modality of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described in connection with FIGS. 1-61. In some aspects, the safety controller **1410** may monitor, by the sensors **1306**, a predetermined relationship between one or more properties of the surgical instrument to detect a fault. A fault may arise when the one or more properties are inconsistent with the predetermined relationship. When the safety controller **1410** determines that a fault exists, an error exists, or that some operation of the plurality of circuit segments was not verified, the safety controller **1410** prevents or disables operation of the particular circuit segment where the fault, error or verification failure originated.

(404) The POST controller **1412** performs a POST to verify proper operation of the plurality of circuit segments. In some aspects, the POST is performed for an individual circuit segment of the plurality of circuit segments prior to the voltage control circuit **1408** applying a voltage to the individual circuit segment to transition the individual circuit segment from standby mode or sleep mode to operational mode. If the individual circuit segment does not pass the POST, the particular circuit segment does not transition from standby mode or sleep mode to operational mode. POST of the handle circuit segment **1416** may comprise, for example, testing whether the handle control sensors **1418** sense an actuation of a handle control of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described in connection with FIGS. 1-61. In some aspects, the POST controller **1412** may transmit a signal to the accelerometer button sensor **1405** to verify the operation of the individual circuit segment as part of the POST. For example, after receiving the signal, the accelerometer button sensor **1405** may prompt a user of the surgical instrument to move the surgical instrument to a plurality of varying locations to confirm operation of the surgical instrument. The accelerometer button sensor **1405** may also monitor an output of a circuit segment or a circuit of a circuit segment as part of the POST. For example, the accelerometer button sensor **1405** can sense an incremental motor pulse generated by the motor **1432** to verify operation. A motor controller of the motor control circuit **1430** may be used to control the motor **1432** to generate the incremental motor pulse.

(405) In various aspects, any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described in connection with FIGS. 1-61 may comprise additional accelerometer button sensors may be used. The POST controller **1412** may also execute a control program stored in the memory

device of the voltage control circuit **1408**. The control program may cause the POST controller **1412** to transmit a signal requesting a matching encrypted parameter from a plurality of circuit segments. Failure to receive a matching encrypted parameter from an individual circuit segment indicates to the POST controller **1412** that the corresponding circuit segment is damaged or malfunctioning. In some aspects, if the POST controller **1412** determines based on the POST that the processor **1302** is damaged or malfunctioning, the POST controller **1412** may send a signal to one or more secondary processors to cause one or more secondary processors to perform critical functions that the processor **1302** is unable to perform. In some aspects, if the POST controller **1412** determines based on the POST that one or more circuit segments do not operate properly, the POST controller **1412** may initiate a reduced performance mode of those circuit segments operating properly while locking out those circuit segments that fail POST or do not operate properly. A locked out circuit segment may function similarly to a circuit segment in standby mode or sleep mode.

(406) The processor circuit segment **1414** comprises the processor **1302** and the volatile memory **1304** described with reference to FIG. **62**. The processor **1302** is configured to initiate an energization or a deenergization sequence. To initiate the energization sequence, the processor **1302** transmits an energizing signal to the voltage control circuit **1408** to cause the voltage control circuit **1408** to apply voltage to the plurality or a subset of the plurality of circuit segments in accordance with the energization sequence. To initiate the deenergization sequence, the processor **1302** transmits a deenergizing signal to the voltage control circuit **1408** to cause the voltage control circuit **1408** to remove voltage from the plurality or a subset of the plurality of circuit segments in accordance with the deenergization sequence.

(407) The handle circuit segment **1416** comprises handle control sensors **1418**. The handle control sensors **1418** may sense an actuation of one or more handle controls of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61**. In various aspects, the one or more handle controls comprise a clamp control, a release button, an articulation switch, an energy activation button, and/or any other suitable handle control. The user may activate the energy activation button to select between an RF energy mode, an ultrasonic energy mode or a combination RF and ultrasonic energy mode. The handle control sensors **1418** may also facilitate attaching a modular handle to the surgical instrument. For example, the handle control sensors **1418** may sense proper attachment of the modular handle to the surgical instrument and indicate the sensed attachment to a user of the surgical instrument. The LCD display **1426** may provide a graphical indication of the sensed attachment. In some aspects, the handle control sensors **1418** senses actuation of the one or more handle controls. Based on the sensed actuation, the processor **1302** may initiate either an energization sequence or a deenergization sequence.

(408) The communication circuit segment **1420** comprises a communication circuit **1422**. The communication circuit **1422** comprises a communication interface to facilitate signal communication between the individual circuit segments of the plurality of circuit segments. In some aspects, the communication circuit **1422** provides a path for the modular components of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61** to communicate electrically. For example, a modular shaft and a modular transducer, when attached together to the handle of the surgical instrument, can upload control programs to the handle through the communication circuit **1422**.

(409) The display circuit segment **1424** comprises a LCD display **1426**. The LCD display **1426** may comprise a liquid crystal display screen, LED indicators, etc. In some aspects, the LCD display **1426** is an organic light-emitting diode (OLED) screen. The Display **226** may be placed on, embedded in, or located remotely from any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61**. For example, the Display **226** can be placed on the handle of the surgical instrument. The Display **226** is configured to provide sensory feedback to a user. In various aspects, the LCD display **1426** further comprises a backlight.

In some aspects, the surgical instrument may also comprise audio feedback devices such as a speaker or a buzzer and tactile feedback devices such as a haptic actuator.

(410) The motor control circuit segment **1428** comprises a motor control circuit **1430** coupled to a motor **1432**. The motor **1432** is coupled to the processor **1302** by a driver and a transistor, such as a FET. In various aspects, the motor control circuit **1430** comprises a motor current sensor in signal communication with the processor **1302** to provide a signal indicative of a measurement of the current draw of the motor to the processor **1302**. The processor transmits the signal to the Display **226**. The Display **226** receives the signal and displays the measurement of the current draw of the motor **1432**. The processor **1302** may use the signal, for example, to monitor that the current draw of the motor **1432** exists within an acceptable range, to compare the current draw to one or more parameters of the plurality of circuit segments, and to determine one or more parameters of a patient treatment site. In various aspects, the motor control circuit **1430** comprises a motor controller to control the operation of the motor. For example, the motor control circuit **1430** controls various motor parameters, such as by adjusting the velocity, torque and acceleration of the motor **1432**. The adjusting is done based on the current through the motor **1432** measured by the motor current sensor.

(411) In various aspects, the motor control circuit **1430** comprises a force sensor to measure the force and torque generated by the motor **1432**. The motor **1432** is configured to actuate a mechanism of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61**. For example, the motor **1432** is configured to control actuation of the shaft of the surgical instrument to realize clamping, rotation and articulation functionality. For example, the motor **1432** may actuate the shaft to realize a clamping motion with jaws of the surgical instrument. The motor controller may determine whether the material clamped by the jaws is tissue or metal. The motor controller may also determine the extent to which the jaws clamp the material. For example, the motor controller may determine how open or closed the jaws are based on the derivative of sensed motor current or motor voltage. In some aspects, the motor **1432** is configured to actuate the transducer to cause the transducer to apply torque to the handle or to control articulation of the surgical instrument. The motor current sensor may interact with the motor controller to set a motor current limit. When the current meets the predefined threshold limit, the motor controller initiates a corresponding change in a motor control operation. For example, exceeding the motor current limit causes the motor controller to reduce the current draw of the motor.

(412) The energy treatment circuit segment **1434** comprises a RF amplifier and safety circuit **1436** and an ultrasonic signal generator circuit **1438** to implement the energy modular functionality of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described in connection with FIGS. **1-61**. In various aspects, the RF amplifier and safety circuit **1436** is configured to control the RF modality of the surgical instrument by generating an RF signal. The ultrasonic signal generator circuit **1438** is configured to control the ultrasonic energy modality by generating an ultrasonic signal. The RF amplifier and safety circuit **1436** and an ultrasonic signal generator circuit **1438** may operate in conjunction to control the combination RF and ultrasonic energy modality.

(413) The shaft circuit segment **1440** comprises a shaft module controller **1442**, a modular control actuator **1444**, one or more end effector sensors **1446**, and a non volatile memory **1448**. The shaft module controller **1442** is configured to control a plurality of shaft modules comprising the control programs to be executed by the processor **1302**. The plurality of shaft modules implements a shaft modality, such as ultrasonic, combination ultrasonic and RF, RF I-blade, and RF-opposable jaw. The shaft module controller **1442** can select shaft modality by selecting the corresponding shaft module for the processor **1302** to execute. The modular control actuator **1444** is configured to actuate the shaft according to the selected shaft modality. After actuation is initiated, the shaft articulates the end effector according to the one or more parameters, routines or programs specific

to the selected shaft modality and the selected end effector modality. The one or more end effector sensors **1446** located at the end effector may include force sensors, temperature sensors, current sensors or motion sensors. The one or more end effector sensors **1446** transmit data about one or more operations of the end effector, based on the energy modality implemented by the end effector. In various aspects, the energy modalities include an ultrasonic energy modality, a RF energy modality, or a combination of the ultrasonic energy modality and the RF energy modality. The non volatile memory **1448** stores the shaft control programs. A control program comprises one or more parameters, routines or programs specific to the shaft. In various aspects, the non volatile memory **1448** may be an ROM, EPROM, EEPROM or flash memory. The non volatile memory **1448** stores the shaft modules corresponding to the selected shaft of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61**. The shaft modules may be changed or upgraded in the non volatile memory **1448** by the shaft module controller **1442**, depending on the surgical instrument shaft to be used in operation.

(414) FIG. **64** illustrates a diagram of one aspect of a surgical instrument **1500** comprising a feedback system for use with any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61**, which may include or implement many of the features described herein. For example, in one aspect, the surgical instrument **1500** may be similar to or representative of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200**. The surgical instrument **1500** may include a generator **1502**. The surgical instrument **1500** also may include an end effector **1506**, which may be activated when a clinician operates a trigger **1510**. In various aspects, the end effector **1506** may include an ultrasonic blade to deliver ultrasonic vibration to carry out surgical coagulation/cutting treatments on living tissue. In other aspects the end effector **1506** may include electrically conductive elements coupled to an electrosurgical high-frequency current energy source to carry out surgical coagulation or cauterization treatments on living tissue and either a mechanical knife with a sharp edge or an ultrasonic blade to carry out cutting treatments on living tissue. When the trigger **1510** is actuated, a force sensor **1512** may generate a signal indicating the amount of force being applied to the trigger **1510**. In addition to, or instead of a force sensor **1512**, the surgical instrument **1500** may include a position sensor **1513**, which may generate a signal indicating the position of the trigger **1510** (e.g., how far the trigger has been depressed or otherwise actuated). In one aspect, the position sensor **1513** may be a sensor positioned with the outer tubular sheath described above or reciprocating tubular actuating member located within the outer tubular sheath described above. In one aspect, the sensor may be a Hall-effect sensor or any suitable transducer that varies its output voltage in response to a magnetic field. The Hall-effect sensor may be used for proximity switching, positioning, speed detection, and current sensing applications. In one aspect, the Hall-effect sensor operates as an analog transducer, directly returning a voltage. With a known magnetic field, its distance from the Hall plate can be determined.

(415) A control circuit **1508** may receive the signals from the sensors **1512** and/or **1513**. The control circuit **1508** may include any suitable analog or digital circuit components. The control circuit **1508** also may communicate with the generator **1502** and/or the transducer **1504** to modulate the power delivered to the end effector **1506** and/or the generator level or ultrasonic blade amplitude of the end effector **1506** based on the force applied to the trigger **1510** and/or the position of the trigger **1510** and/or the position of the outer tubular sheath described above relative to the reciprocating tubular actuating member **58** located within the outer tubular sheath **56** described above (e.g., as measured by a Hall-effect sensor and magnet combination). For example, as more force is applied to the trigger **1510**, more power and/or a higher ultrasonic blade amplitude may be delivered to the end effector **1506**. According to various aspects, the force sensor **1512** may be replaced by a multi-position switch.

(416) According to various aspects, the end effector **1506** may include a clamp or clamping mechanism, for example, such as that described above with respect to FIGS. **1-5**. When the trigger

1510 is initially actuated, the clamping mechanism may close, clamping tissue between a clamp arm and the end effector **1506**. As the force applied to the trigger increases (e.g., as sensed by force sensor **1512**) the control circuit **1508** may increase the power delivered to the end effector **1506** by the transducer **1504** and/or the generator level or ultrasonic blade amplitude brought about in the end effector **1506**. In one aspect, trigger position, as sensed by position sensor **1513** or clamp or clamp arm position, as sensed by position sensor **1513** (e.g., with a Hall-effect sensor), may be used by the control circuit **1508** to set the power and/or amplitude of the end effector **1506**. For example, as the trigger is moved further towards a fully actuated position, or the clamp or clamp arm moves further towards the ultrasonic blade (or end effector **1506**), the power and/or amplitude of the end effector **1506** may be increased.

(417) According to various aspects, the surgical instrument **1500** also may include one or more feedback devices for indicating the amount of power delivered to the end effector **1506**. For example, a speaker **1514** may emit a signal indicative of the end effector power. According to various aspects, the speaker **1514** may emit a series of pulse sounds, where the frequency of the sounds indicates power. In addition to, or instead of the speaker **1514**, the surgical instrument **1500** may include a visual display **1516**. The visual display **1516** may indicate end effector power according to any suitable method. For example, the visual display **1516** may include a series of LEDs, where end effector power is indicated by the number of illuminated LEDs. The speaker **1514** and/or visual display **1516** may be driven by the control circuit **1508**. According to various aspects, the surgical instrument **1500** may include a ratcheting device (not shown) connected to the trigger **1510**. The ratcheting device may generate an audible sound as more force is applied to the trigger **1510**, providing an indirect indication of end effector power. The surgical instrument **1500** may include other features that may enhance safety. For example, the control circuit **1508** may be configured to prevent power from being delivered to the end effector **1506** in excess of a predetermined threshold. Also, the control circuit **1508** may implement a delay between the time when a change in end effector power is indicated (e.g., by speaker **1514** or visual display **1516**), and the time when the change in end effector power is delivered. In this way, a clinician may have ample warning that the level of ultrasonic power that is to be delivered to the end effector **1506** is about to change.

(418) In one aspect, the ultrasonic or high-frequency current generators of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61** may be configured to generate the electrical signal waveform digitally such that the desired using a predetermined number of phase points stored in a lookup table to digitize the wave shape. The phase points may be stored in a table defined in a memory, a field programmable gate array (FPGA), or any suitable non-volatile memory. FIG. **65** illustrates one aspect of a fundamental architecture for a digital synthesis circuit such as a direct digital synthesis (DDS) circuit **1600** configured to generate a plurality of wave shapes for the electrical signal waveform. The generator software and digital controls may command the FPGA to scan the addresses in the lookup table **1604** which in turn provides varying digital input values to a DAC circuit **1608** that feeds a power amplifier. The addresses may be scanned according to a frequency of interest. Using such a lookup table **1604** enables generating various types of wave shapes that can be fed into tissue or into a transducer, an RF electrode, multiple transducers simultaneously, multiple RF electrodes simultaneously, or a combination of RF and ultrasonic instruments. Furthermore, multiple lookup tables **1604** that represent multiple wave shapes can be created, stored, and applied to tissue from a generator.

(419) The waveform signal may be configured to control at least one of an output current, an output voltage, or an output power of an ultrasonic transducer and/or an RF electrode, or multiples thereof (e.g. two or more ultrasonic transducers and/or two or more RF electrodes). Further, where the surgical instrument comprises an ultrasonic components, the waveform signal may be configured to drive at least two vibration modes of an ultrasonic transducer of the at least one surgical

instrument. Accordingly, a generator may be configured to provide a waveform signal to at least one surgical instrument wherein the waveform signal corresponds to at least one wave shape of a plurality of wave shapes in a table. Further, the waveform signal provided to the two surgical instruments may comprise two or more wave shapes. The table may comprise information associated with a plurality of wave shapes and the table may be stored within the generator. In one aspect or example, the table may be a direct digital synthesis table, which may be stored in an FPGA of the generator. The table may be addressed by anyway that is convenient for categorizing wave shapes. According to one aspect, the table, which may be a direct digital synthesis table, is addressed according to a frequency of the waveform signal. Additionally, the information associated with the plurality of wave shapes may be stored as digital information in the table.

(420) The analog electrical signal waveform may be configured to control at least one of an output current, an output voltage, or an output power of an ultrasonic transducer and/or an RF electrode, or multiples thereof (e.g., two or more ultrasonic transducers and/or two or more RF electrodes). Further, where the surgical instrument comprises ultrasonic components, the analog electrical signal waveform may be configured to drive at least two vibration modes of an ultrasonic transducer of the at least one surgical instrument. Accordingly, the generator circuit may be configured to provide an analog electrical signal waveform to at least one surgical instrument wherein the analog electrical signal waveform corresponds to at least one wave shape of a plurality of wave shapes stored in a lookup table **1604**. Further, the analog electrical signal waveform provided to the two surgical instruments may comprise two or more wave shapes. The lookup table **1604** may comprise information associated with a plurality of wave shapes and the lookup table **1604** may be stored either within the generator circuit or the surgical instrument. In one aspect or example, the lookup table **1604** may be a direct digital synthesis table, which may be stored in an FPGA of the generator circuit or the surgical instrument. The lookup table **1604** may be addressed by anyway that is convenient for categorizing wave shapes. According to one aspect, the lookup table **1604**, which may be a direct digital synthesis table, is addressed according to a frequency of the desired analog electrical signal waveform. Additionally, the information associated with the plurality of wave shapes may be stored as digital information in the lookup table **1604**.

(421) With the widespread use of digital techniques in instrumentation and communications systems, a digitally-controlled method of generating multiple frequencies from a reference frequency source has evolved and is referred to as direct digital synthesis. The basic architecture is shown in FIG. **65**. In this simplified block diagram, a DDS circuit is coupled to a processor, controller, or a logic device of the generator circuit and to a memory circuit located either in the generator circuit of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61**. The DDS circuit **1600** comprises an address counter **1602**, lookup table **1604**, a register **1606**, a DAC circuit **1608**, and a filter **1612**. A stable clock $f_{sub.c}$ is received by the address counter **1602** and the register **1606** drives a programmable-read-only-memory (PROM) which stores one or more integral number of cycles of a sinewave (or other arbitrary waveform) in a lookup table **1604**. As the address counter **1602** steps through memory locations, values stored in the lookup table **1604** are written to a register **1606**, which is coupled to a DAC circuit **1608**. The corresponding digital amplitude of the signal at the memory location of the lookup table **1604** drives the DAC circuit **1608**, which in turn generates an analog output signal **1610**. The spectral purity of the analog output signal **1610** is determined primarily by the DAC circuit **1608**. The phase noise is basically that of the reference clock $f_{sub.c}$. The first analog output signal **1610** output from the DAC circuit **1608** is filtered by the filter **1612** and a second analog output signal **1614** output by the filter **1612** is provided to an amplifier having an output coupled to the output of the generator circuit. The second analog output signal has a frequency $f_{sub.out}$.

(422) Because the DDS circuit **1600** is a sampled data system, issues involved in sampling must be considered: quantization noise, aliasing, filtering, etc. For instance, the higher order harmonics of

the DAC circuit **1608** output frequencies fold back into the Nyquist bandwidth, making them unfilterable, whereas, the higher order harmonics of the output of phase-locked-loop (PLL) based synthesizers can be filtered. The lookup table **1604** contains signal data for an integral number of cycles. The final output frequency $f_{sub.out}$ can be changed changing the reference clock frequency $f_{sub.c}$ or by reprogramming the PROM.

(423) The DDS circuit **1600** may comprise multiple lookup tables **1604** where the lookup table **1604** stores a waveform represented by a predetermined number of samples, wherein the samples define a predetermined shape of the waveform. Thus multiple waveforms having a unique shape can be stored in multiple lookup tables **1604** to provide different tissue treatments based on instrument settings or tissue feedback. Examples of waveforms include high crest factor RF electrical signal waveforms for surface tissue coagulation, low crest factor RF electrical signal waveform for deeper tissue penetration, and electrical signal waveforms that promote efficient touch-up coagulation. In one aspect, the DDS circuit **1600** can create multiple wave shape lookup tables **1604** and during a tissue treatment procedure (e.g., “on-the-fly” or in virtual real time based on user or sensor inputs) switch between different wave shapes stored in separate lookup tables **1604** based on the tissue effect desired and/or tissue feedback. Accordingly, switching between wave shapes can be based on tissue impedance and other factors, for example. In other aspects, the lookup tables **1604** can store electrical signal waveforms shaped to maximize the power delivered into the tissue per cycle (i.e., trapezoidal or square wave). In other aspects, the lookup tables **1604** can store wave shapes synchronized in such way that they make maximizing power delivery by the multifunction surgical instrument any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61** while delivering RF and ultrasonic drive signals. In yet other aspects, the lookup tables **1604** can store electrical signal waveforms to drive ultrasonic and RF therapeutic, and/or sub-therapeutic, energy simultaneously while maintaining ultrasonic frequency lock. Custom wave shapes specific to different instruments and their tissue effects can be stored in the non-volatile memory of the generator circuit or in the non-volatile memory (e.g., EEPROM) of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61** and be fetched upon connecting the multifunction surgical instrument to the generator circuit. An example of an exponentially damped sinusoid, as used in many high crest factor “coagulation” waveforms is shown in FIG. **67**.

(424) A more flexible and efficient implementation of the DDS circuit **1600** employs a digital circuit called a Numerically Controlled Oscillator (NCO). A block diagram of a more flexible and efficient digital synthesis circuit such as a DDS circuit **1700** is shown in FIG. **66**. In this simplified block diagram, a DDS circuit **1700** is coupled to a processor, controller, or a logic device of the generator and to a memory circuit located either in the generator or in any of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61**. The DDS circuit **1700** comprises a load register **1702**, a parallel delta phase register **1704**, an adder circuit **1716**, a phase register **1708**, a lookup table **1710** (phase-to-amplitude converter), a DAC circuit **1712**, and a filter **1714**. The adder circuit **1716** and the phase register **1708** form part of a phase accumulator **1706**. A clock signal $f_{sub.c}$ is applied to the phase register **1708** and the DAC circuit **1712**. The load register **1702** receives a tuning word that specifies output frequency as a fraction of the reference clock frequency $f_{sub.c}$. The output of the load register **1702** is provided to a parallel delta phase register **1704** with a tuning word M .

(425) The DDS circuit **1700** includes a sample clock that generates a clock frequency $f_{sub.c}$, a phase accumulator **1706**, and a lookup table **1710** (e.g., phase to amplitude converter). The content of the phase accumulator **1706** is updated once per clock cycle $f_{sub.c}$. When time the phase accumulator **1706** is updated, the digital number, M , stored in the parallel delta phase register **1704** is added to the number in the phase register **1708** by an adder circuit **1716**. Assuming that the number in the parallel delta phase register **1704** is $00 \dots 01$ and that the initial contents of the phase accumulator **1706** is $00 \dots 00$. The phase accumulator **1706** is updated by $00 \dots 01$ per

clock cycle. If the phase accumulator **1706** is 32-bits wide, 232 clock cycles (over 4 billion) are required before the phase accumulator **1706** returns to 00 . . . 00, and the cycle repeats.

(426) The truncated output **1718** of the phase accumulator **1706** is provided to a phase-to amplitude converter lookup table **1710** and the output of the lookup table **1710** is coupled to a DAC circuit **1712**. The truncated output **1718** of the phase accumulator **1706** serves as the address to a sine (or cosine) lookup table. An address in the lookup table corresponds to a phase point on the sinewave from 0° to 360°. The lookup table **1710** contains the corresponding digital amplitude information for one complete cycle of a sinewave. The lookup table **1710** therefore maps the phase information from the phase accumulator **1706** into a digital amplitude word, which in turn drives the DAC circuit **1712**. The output of the DAC circuit is a first analog signal **1720** and is filtered by a filter **1714**. The output of the filter **1714** is a second analog signal **1722**, which is provided to a power amplifier coupled to the output of the generator circuit.

(427) In one aspect, the electrical signal waveform may be digitized into 1024 (210) phase points, although the wave shape may be digitized is any suitable number of 2ⁿ phase points ranging from 256 (28) to 281,474,976,710,656 (248), where n is a positive integer, as shown in TABLE 1. The electrical signal waveform may be expressed as A_n(θ_n), where a normalized amplitude A_n at a point n is represented by a phase angle θ_n is referred to as a phase point at point n. The number of discrete phase points n determines the tuning resolution of the DDS circuit **1700** (as well as the DDS circuit **1600** shown in FIG. 65).

(428) TABLE-US-00001 TABLE 1 N Number of Phase Points 2^{sup.n} 8 256 10 1,024 12 4,096 14 16,384 16 65,536 18 262,144 20 1,048,576 22 4,194,304 24 16,777,216 26 67,108,864 28 268,435,456 32 4,294,967,296 48 281,474,976,710,656

(429) The generator circuit algorithms and digital control circuits scan the addresses in the lookup table **1710**, which in turn provides varying digital input values to the DAC circuit **1712** that feeds the filter **1714** and the power amplifier. The addresses may be scanned according to a frequency of interest. Using the lookup table enables generating various types of shapes that can be converted into an analog output signal by the DAC circuit **1712**, filtered by the filter **1714**, amplified by the power amplifier coupled to the output of the generator circuit, and fed to the tissue in the form of RF energy or fed to an ultrasonic transducer and applied to the tissue in the form of ultrasonic vibrations which deliver energy to the tissue in the form of heat. The output of the amplifier can be applied to an RF electrode, multiple RF electrodes simultaneously, an ultrasonic transducer, multiple ultrasonic transducers simultaneously, or a combination of RF and ultrasonic transducers, for example. Furthermore, multiple wave shape tables can be created, stored, and applied to tissue from a generator circuit.

(430) With reference back to FIG. 65, for n=32, and M=1, the phase accumulator **1706** steps through 232 possible outputs before it overflows and restarts. The corresponding output wave frequency is equal to the input clock frequency divided by 232. If M=2, then the phase register **1708** “rolls over” twice as fast, and the output frequency is doubled. This can be generalized as follows.

(431) For a phase accumulator **1706** configured to accumulate n-bits (n generally ranges from 24 to 32 in most DDS systems, but as previously discussed n may be selected from a wide range of options), there are 2^{sup.n} possible phase points. The digital word in the delta phase register, M, represents the amount the phase accumulator is incremented per clock cycle. If f_c is the clock frequency, then the frequency of the output sinewave is equal to:

$$(432) f_o = \frac{M \cdot \text{Math. } f_c}{2^n} \quad \text{Eq. 1}$$

(433) Equation 1 is known as the DDS “tuning equation” Note that the frequency resolution of the system is equal to

$$(434) \frac{f_o}{2^n}.$$

For n=32, the resolution is greater than one part in four billion. In one aspect of the DDS circuit

1700, not all of the bits out of the phase accumulator **1706** are passed on to the lookup table **1710**, but are truncated, leaving only the first **13** to **15** most significant bits (MSBs), for example. This reduces the size of the lookup table **1710** and does not affect the frequency resolution. The phase truncation only adds a small but acceptable amount of phase noise to the final output.

(435) The electrical signal waveform may be characterized by a current, voltage, or power at a predetermined frequency. Further, where any one of the surgical instruments **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-61** comprises ultrasonic components, the electrical signal waveform may be configured to drive at least two vibration modes of an ultrasonic transducer of the at least one surgical instrument. Accordingly, the generator circuit may be configured to provide an electrical signal waveform to at least one surgical instrument wherein the electrical signal waveform is characterized by a predetermined wave shape stored in the lookup table **1710** (or lookup table **1604** FIG. **65**). Further, the electrical signal waveform may be a combination of two or more wave shapes. The lookup table **1710** may comprise information associated with a plurality of wave shapes. In one aspect or example, the lookup table **1710** may be generated by the DDS circuit **1700** and may be referred to as a direct digital synthesis table. DDS works by first storing a large repetitive waveform in onboard memory. A cycle of a waveform (sine, triangle, square, arbitrary) can be represented by a predetermined number of phase points as shown in TABLE 1 and stored into memory. Once the waveform is stored into memory, it can be generated at very precise frequencies. The direct digital synthesis table may be stored in a non-volatile memory of the generator circuit and/or may be implemented with a FPGA circuit in the generator circuit. The lookup table **1710** may be addressed by any suitable technique that is convenient for categorizing wave shapes. According to one aspect, the lookup table **1710** is addressed according to a frequency of the electrical signal waveform. Additionally, the information associated with the plurality of wave shapes may be stored as digital information in a memory or as part of the lookup table **1710**.

(436) In one aspect, the generator circuit may be configured to provide electrical signal waveforms to at least two surgical instruments simultaneously. The generator circuit also may be configured to provide the electrical signal waveform, which may be characterized two or more wave shapes, via an output channel of the generator circuit to the two surgical instruments simultaneously. For example, in one aspect the electrical signal waveform comprises a first electrical signal to drive an ultrasonic transducer (e.g., ultrasonic drive signal), a second RF drive signal, and/or a combination thereof. In addition, an electrical signal waveform may comprise a plurality of ultrasonic drive signals, a plurality of RF drive signals, and/or a combination of a plurality of ultrasonic and RF drive signals.

(437) In addition, a method of operating the generator circuit according to the present disclosure comprises generating an electrical signal waveform and providing the generated electrical signal waveform to any one of the surgical instruments **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-61**, where generating the electrical signal waveform comprises receiving information associated with the electrical signal waveform from a memory. The generated electrical signal waveform comprises at least one wave shape. Furthermore, providing the generated electrical signal waveform to the at least one surgical instrument comprises providing the electrical signal waveform to at least two surgical instruments simultaneously.

(438) The generator circuit as described herein may allow for the generation of various types of direct digital synthesis tables. Examples of wave shapes for RF/Electrosurgery signals suitable for treating a variety of tissue generated by the generator circuit include RF signals with a high crest factor (which may be used for surface coagulation in RF mode), a low crest factor RF signals (which may be used for deeper tissue penetration), and waveforms that promote efficient touch-up coagulation. The generator circuit also may generate multiple wave shapes employing a direct digital synthesis lookup table **1710** and, on the fly, can switch between particular wave shapes based on the desired tissue effect. Switching may be based on tissue impedance and/or other

factors.

(439) In addition to traditional sine/cosine wave shapes, the generator circuit may be configured to generate wave shape(s) that maximize the power into tissue per cycle (i.e., trapezoidal or square wave). The generator circuit may provide wave shape(s) that are synchronized to maximize the power delivered to the load when driving RF and ultrasonic signals simultaneously and to maintain ultrasonic frequency lock, provided that the generator circuit includes a circuit topology that enables simultaneously driving RF and ultrasonic signals. Further, custom wave shapes specific to instruments and their tissue effects can be stored in a non-volatile memory (NVM) or an instrument EEPROM and can be fetched upon connecting any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61** to the generator circuit.

(440) The DDS circuit **1700** may comprise multiple lookup tables **1604** where the lookup table **1710** stores a waveform represented by a predetermined number of phase points (also may be referred to as samples), wherein the phase points define a predetermined shape of the waveform. Thus multiple waveforms having a unique shape can be stored in multiple lookup tables **1710** to provide different tissue treatments based on instrument settings or tissue feedback. Examples of waveforms include high crest factor RF electrical signal waveforms for surface tissue coagulation, low crest factor RF electrical signal waveform for deeper tissue penetration, and electrical signal waveforms that promote efficient touch-up coagulation. In one aspect, the DDS circuit **1700** can create multiple wave shape lookup tables **1710** and during a tissue treatment procedure (e.g., “on-the-fly” or in virtual real time based on user or sensor inputs) switch between different wave shapes stored in different lookup tables **1710** based on the tissue effect desired and/or tissue feedback. Accordingly, switching between wave shapes can be based on tissue impedance and other factors, for example. In other aspects, the lookup tables **1710** can store electrical signal waveforms shaped to maximize the power delivered into the tissue per cycle (i.e., trapezoidal or square wave). In other aspects, the lookup tables **1710** can store wave shapes synchronized in such way that they make maximizing power delivery by any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-61** when delivering RF and ultrasonic drive signals. In yet other aspects, the lookup tables **1710** can store electrical signal waveforms to drive ultrasonic and RF therapeutic, and/or sub-therapeutic, energy simultaneously while maintaining ultrasonic frequency lock. Generally, the output wave shape may be in the form of a sine wave, cosine wave, pulse wave, square wave, and the like. Nevertheless, the more complex and custom wave shapes specific to different instruments and their tissue effects can be stored in the non-volatile memory of the generator circuit or in the non-volatile memory (e.g., EEPROM) of the surgical instrument and be fetched upon connecting the surgical instrument to the generator circuit. One example of a custom wave shape is an exponentially damped sinusoid as used in many high crest factor “coagulation” waveforms, as shown in FIG. **67**.

(441) FIG. **67** illustrates one cycle of a discrete time digital electrical signal waveform **1800**, according to one aspect of the present disclosure of an analog waveform **1804** (shown superimposed over the discrete time digital electrical signal waveform **1800** for comparison purposes). The horizontal axis represents Time (t) and the vertical axis represents digital phase points. The digital electrical signal waveform **1800** is a digital discrete time version of the desired analog waveform **1804**, for example. The digital electrical signal waveform **1800** is generated by storing an amplitude phase point **1802** that represents the amplitude per clock cycle Talk over one cycle or period T.sub.o. The digital electrical signal waveform **1800** is generated over one period T.sub.o by any suitable digital processing circuit. The amplitude phase points are digital words stored in a memory circuit. In the example illustrated in FIGS. **65, 66**, the digital word is a six-bit word that is capable of storing the amplitude phase points with a resolution of 26 or 64 bits. It will be appreciated that the examples shown in FIGS. **65, 66** is for illustrative purposes and in actual implementations the resolution can be much higher. The digital amplitude phase points **1802** over one cycle T.sub.o are stored in the memory as a string of string words in a lookup table **1604, 1710**

as described in connection with FIGS. 65, 66, for example. To generate the analog version of the analog waveform **1804**, the amplitude phase points **1802** are read sequentially from the memory from 0 to T.sub.o per clock cycle T.sub.clk and are converted by a DAC circuit **1608**, **1712**, also described in connection with FIGS. 65, 66. Additional cycles can be generated by repeatedly reading the amplitude phase points **1802** of the digital electrical signal waveform **1800** the from 0 to T.sub.o for as many cycles or periods as may be desired. The smooth analog version of the analog waveform **1804** is achieved by filtering the output of the DAC circuit **1608**, **1712** by a filter **1612**, **1714** (FIGS. 65 and 66). The filtered analog output signal **1614**, **1722** (FIGS. 65 and 66) is applied to the input of a power amplifier.

(442) In one aspect, as illustrated in FIG. 68A, a circuit **1900** may comprise a controller comprising one or more processors **1902** (e.g., microprocessor, microcontroller) coupled to at least one memory circuit **1904**. The at least one memory circuit **1904** stores machine executable instructions that when executed by the processor **1902**, cause the processor **1902** to execute machine instructions to implement any of the algorithms, processes, or techniques described herein.

(443) The processor **1902** may be any one of a number of single or multi-core processors known in the art. The memory circuit **1904** may comprise volatile and non-volatile storage media. In one aspect, as illustrated in FIG. 68A, the processor **1902** may include an instruction processing unit **1906** and an arithmetic unit **1908**. The instruction processing unit may be configured to receive instructions from the one memory circuit **1904**.

(444) In one aspect, a circuit **1910** may comprise a finite state machine comprising a combinational logic circuit **1912**, as illustrated in FIG. 68B, configured to implement any of the algorithms, processes, or techniques described herein. In one aspect, a circuit **1920** may comprise a finite state machine comprising a sequential logic circuit, as illustrated in FIG. 68C. The sequential logic circuit **1920** may comprise the combinational logic circuit **1912** and at least one memory circuit **1914**, for example. The at least one memory circuit **1914** can store a current state of the finite state machine, as illustrated in FIG. 68C. The sequential logic circuit **1920** or the combinational logic circuit **1912** can be configured to implement any of the algorithms, processes, or techniques described herein. In certain instances, the sequential logic circuit **1920** may be synchronous or asynchronous.

(445) In other aspects, the circuit may comprise a combination of the processor **1902** and the finite state machine to implement any of the algorithms, processes, or techniques described herein. In other aspects, the finite state machine may comprise a combination of the combinational logic circuit **1910** and the sequential logic circuit **1920**.

(446) FIG. 69 is a schematic diagram of a circuit **1925** of various components of a surgical instrument with motor control functions, according to one aspect of the present disclosure. In various aspects, the surgical instruments **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. 1-68C may include a drive mechanism **1930** which is configured to drive shafts and/or gear components in order to perform the various operations associated with the surgical instruments **100**, **480**, **500**, **600**, **1100**, **1150**, **1200**. In one aspect, the drive mechanism **1930** includes a rotation drivetrain **1932** configured to rotate end effector **112**, **512**, **1000**, **1112**, **1212** as described in connection with FIGS. 1, 20, 40, 41, 45, 54, for example, about a longitudinal axis relative to handle housing. The drive mechanism **1930** further includes a closure drivetrain **1934** configured to close a jaw member to grasp tissue with the end effector. In addition, the drive mechanism **1930** includes a firing drive train **1936** configured to fire an I-beam knife of the end effector to cut tissue grasped by the end effector.

(447) The drive mechanism **1930** includes a selector gearbox assembly **1938** that can be located in the handle assembly of the surgical instrument. Proximal to the selector gearbox assembly **1938** is a function selection module which includes a first motor **1942** that functions to selectively move gear elements within the selector gearbox assembly **1938** to selectively position one of the drivetrains **1932**, **1934**, **1936** into engagement with an input drive component of an optional second motor

1944 and motor drive circuit **1946** (shown in dashed line to indicate that the second motor **1944** and motor drive circuit **1946** are optional components).

(448) Still referring to FIG. **69**, the motors **1942**, **1944** are coupled to motor control circuits **1946**, **1948**, respectively, which are configured to control the operation of the motors **1942**, **1944** including the flow of electrical energy from a power source **1950** to the motors **1942**, **1944**. The power source **1950** may be a DC battery (e.g., rechargeable lead-based, nickel-based, lithium-ion based, battery etc.) or any other power source suitable for providing electrical energy to the surgical instrument.

(449) The surgical instrument further includes a microcontroller **1952** (“controller”). In certain instances, the controller **1952** may include a microprocessor **1954** (“processor”) and one or more computer readable mediums or memory units **1956** (“memory”). In certain instances, the memory **1956** may store various program instructions, which when executed may cause the processor **1954** to perform a plurality of functions and/or calculations described herein. The power source **1950** can be configured to supply power to the controller **1952**, for example.

(450) The processor **1954** be in communication with the motor control circuit **1946**. In addition, the memory **1956** may store program instructions, which when executed by the processor **1954** in response to a user input **1958** or feedback elements **1960**, may cause the motor control circuit **1946** to motivate the motor **1942** to generate at least one rotational motion to selectively move gear elements within the selector gearbox assembly **1938** to selectively position one of the drivetrains **1932**, **1934**, **1936** into engagement with the input drive component of the second motor **1944**. Furthermore, the processor **1954** can be in communication with the motor control circuit **1948**. The memory **1956** also may store program instructions, which when executed by the processor **1954** in response to a user input **1958**, may cause the motor control circuit **1948** to motivate the motor **1944** to generate at least one rotational motion to drive the drivetrain engaged with the input drive component of the second motor **1948**, for example.

(451) The controller **1952** and/or other controllers of the present disclosure may be implemented using integrated and/or discrete hardware elements, software elements, and/or a combination of both. Examples of integrated hardware elements may include processors, microprocessors, microcontrollers, integrated circuits, ASICs, PLDs, DSPs, FPGAs, logic gates, registers, semiconductor devices, chips, microchips, chip sets, microcontrollers, system on a chip (SoC), and/or single in-line package (SIP). Examples of discrete hardware elements may include circuits and/or circuit elements such as logic gates, field effect transistors, bipolar transistors, resistors, capacitors, inductors, and/or relays. In certain instances, the controller **1952** may include a hybrid circuit comprising discrete and integrated circuit elements or components on one or more substrates, for example.

(452) In certain instances, the controller **1952** and/or other controllers of the present disclosure may be an LM 4F230H5QR, available from Texas Instruments, for example. In certain instances, the Texas Instruments LM4F230H5QR is an ARM Cortex-M4F Processor Core comprising on-chip memory of 256 KB single-cycle flash memory, or other non-volatile memory, up to 40 MHz, a prefetch buffer to improve performance above 40 MHz, a 32 KB single-cycle SRAM, internal ROM loaded with StellarisWare® software, 2 KB EEPROM, one or more PWM modules, one or more QEI analog, one or more 12-bit ADC with 12 analog input channels, among other features that are readily available. Other microcontrollers may be readily substituted for use with the present disclosure. Accordingly, the present disclosure should not be limited in this context.

(453) In various instances, one or more of the various steps described herein can be performed by a finite state machine comprising either a combinational logic circuit or a sequential logic circuit, where either the combinational logic circuit or the sequential logic circuit is coupled to at least one memory circuit. The at least one memory circuit stores a current state of the finite state machine. The combinational or sequential logic circuit is configured to cause the finite state machine to the steps. The sequential logic circuit may be synchronous or asynchronous. In other instances, one or

more of the various steps described herein can be performed by a circuit that includes a combination of the processor **1958** and the finite state machine, for example.

(454) In various instances, it can be advantageous to be able to assess the state of the functionality of a surgical instrument to ensure its proper function. It is possible, for example, for the drive mechanism, as explained above, which is configured to include various motors, drivetrains, and/or gear components in order to perform the various operations of the surgical instrument, to wear out over time. This can occur through normal use, and in some instances the drive mechanism can wear out faster due to abuse conditions. In certain instances, a surgical instrument can be configured to perform self-assessments to determine the state, e.g. health, of the drive mechanism and its various components.

(455) For example, the self-assessment can be used to determine when the surgical instrument is capable of performing its function before a re-sterilization or when some of the components should be replaced and/or repaired. Assessment of the drive mechanism and its components, including but not limited to the rotation drivetrain **1932**, the closure drivetrain **1934**, and/or the firing drivetrain **1936**, can be accomplished in a variety of ways. The magnitude of deviation from a predicted performance can be used to determine the likelihood of a sensed failure and the severity of such failure. Several metrics can be used including: Periodic analysis of repeatably predictable events, Peaks or drops that exceed an expected threshold, and width of the failure.

(456) In various instances, a signature waveform of a properly functioning drive mechanism or one or more of its components can be employed to assess the state of the drive mechanism or the one or more of its components. One or more vibration sensors can be arranged with respect to a properly functioning drive mechanism or one or more of its components to record various vibrations that occur during operation of the properly functioning drive mechanism or the one or more of its components. The recorded vibrations can be employed to create the signature waveform. Future waveforms can be compared against the signature waveform to assess the state of the drive mechanism and its components.

(457) Still referring to FIG. **69**, the surgical instrument **1930** includes a drivetrain failure detection module **1962** configured to record and analyze one or more acoustic outputs of one or more of the drivetrains **1932**, **1934**, **1936**. The processor **1954** can be in communication with or otherwise control the module **1962**. As described below in greater detail, the module **1962** can be embodied as various means, such as circuitry, hardware, a computer program product comprising a computer readable medium (for example, the memory **1956**) storing computer readable program instructions that are executable by a processing device (for example, the processor **1954**), or some combination thereof. In some aspects, the processor **36** can include, or otherwise control the module **1962**.

(458) FIG. **70** illustrates a handle assembly **1970** with a removable service panel **1972** removed to shown internal components of the handle assembly, according to one aspect of the present disclosure. The removable service panel **1972**, or removable service cover, also includes reinforcing ribs **1990** for strength. The removable service panel **1972** comprises a plurality of fasteners **1988** that mate with a plurality of fasteners **1986** on the handle housing **1974** to removably attach the removable service panel **1972** to the handle housing **1974**. In one aspect, the fasteners **1988** in the removable service panel **1972** comprise a first set of magnets and the handle housing **1974** comprises a second set of magnets that magnetically latch the service panel **1972** to the handle housing **1974**. In one aspect, the first and second set of magnets **6112a**, **6112b** are rare-earth permanent magnets.

(459) In FIG. **70**, the removable service panel **1972** is shown removed from the handle housing **1974** to show the location of electrical and mechanical components of the surgical instrument such as the motor **1976** and electrical contacts **1984** to electrically couple the battery assembly or flexible circuits to the handle housing **1974**. The motor **1976** and the electrical contacts **1984** are also removable from the handle housing **1974**. The handle assembly **1970** also comprises a trigger **1982** and an actuation switch **1980**, each of which is removable from the handle housing **1974**. As

previously described, the removable trigger **1982** may have multiple stages of operation to close the jaw member, fire the knife, activate the ultrasonic transducer, activate the high-frequency current, and/or open the jaw member. The actuation switch **1980** may be replaced with multiple switches to activate different functions such as, for example, close the jaw member, fire the knife, activate the ultrasonic transducer, activate the high-frequency current, and/or open the jaw member. As shown in FIG. **70**, the handle assembly **1970** includes electrical contacts **1978** to electrically couple the handle assembly **1970** to the shaft assembly, where the electrical contacts **1978** are removable from the handle housing **1974**. The handle housing **1974** also defines a space to receive a removable ultrasonic transducer assembly, ultrasonic transducer, ultrasonic transducer drive circuits, high-frequency current drive circuits, and/or display assembly, as previously discussed herein.

Modular Battery Powered Handheld Surgical Instrument with Selective Application of Energy Based on Tissue Characterization and with Selective Application of Energy Based on Button Displacement, Intensity, or Local Tissue Characterization

(460) In one aspect, the present disclosure provides a modular battery powered handheld surgical instrument with selective application of energy based on tissue characterization. Disclosed is a surgical instrument that includes a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle assembly; a radio frequency (RF) energy output powered by the battery assembly and configured to apply RF energy to a tissue; an ultrasonic energy output powered by the battery assembly and configured to apply ultrasonic energy to the tissue; and a controller configured to, based at least in part on a measured tissue characteristic, start application of RF energy by the RF energy output or application of ultrasonic energy by the ultrasonic energy output at a first time.

(461) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with selective application of energy based on button displacement, intensity, or local tissue characterization. Disclosed is a surgical instrument that includes a controller configured to control application of RF or ultrasonic energy at a low level when displacement or intensity of a button is above a first threshold but below a second threshold higher than the first threshold, and control application of RF or ultrasonic energy at a high level when the displacement or intensity exceeds the second threshold. In another aspect, a surgical instrument comprises a first sensor configured to measure a tissue characteristic at a first location, a second sensor configured to measure the tissue characteristic at a second location, and a controller configured to, based at least in part on the measured tissue characteristic at the first location and the second location, control application of RF or ultrasonic energy.

(462) FIGS. **71-81** illustrate one aspect of the present disclosure that is directed to switching between energy modalities such as high-frequency (e.g., RF), ultrasonic, or a combination of high-frequency current and ultrasonic energy modalities automatically based on a sensed/calculated measure of a parameter of the surgical instrument **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-70** implying tissue thickness and/or type based on (impedance, current from the motor, jaw gap sensing, tissue compression, temperature, and the like. The first portion describes an example system wherein a change of energy modality is done based on the measure of tissue thickness by the combination of at least two measures of tissue parameters (impedance, current from the motor, jaw gap sensing, tissue compression, temperature). In one aspect, impedance, force, and velocity/displacement are measured to control energy modality of a combo ultrasonic/RF device. Measurement of force is used to determine the type of energy modality that can be used and indicate the timing at which the user can selectively switch if desired in an ultrasonic/RF combo device. One technique to accomplish this is by utilizing the slope of the motor current to dictate the ultrasonic, RF, or both energy modes. Another option is to use the rate of change of a measurable tissue characteristic to determine the energy modality which can be used

(RF or Ultrasonic) or where in the cycle to start or stop using a specific energy modality. Again, the slope of the impedance may be utilized to dictate the ultrasonic, RF, or both energy modes.

(463) Another technique to accomplish control of energy modality is by sensing of tissue gap by a rotary encoder, attached to the trigger or the clamp arm of the device or by measuring tissue thickness to set modality decision of the energy mode. In this scenario, wider gap indicates touch-up or debulking function is required while narrow gap indicates vessel sealing mode. Additionally, the maximum applicable power may be changed based on the slope and intensity of the impedance measured in order to only effect the raising portion of the impedance bath tub.

(464) Yet another technique to accomplish control of energy modality is through motor current thresholds which indicate thickness of tissue and define energy modality options available and/or initiate switching of energy application levels or modes based on predefined levels. For instance, specific motor controls can be based on tissue parameters. As an example, wait and energy profile changes can be made due to sensing different tissue characteristics and types. Or a motor control circuit can be employed which increases the motor current for a motorized device closure and therefore increases forces at the end of the impedance curve for an ultrasonic and increases closure force in order to finish the cut cleanly. Although many of these embodiments may be done using tissue measurements, an alternative embodiment would be to measure the forces on the clamp arm directly through some form of force transducer. Some methods to measure tissue type, thickness and other parameters include tissue thickness sensing as part of closure. This may be done by pre-defining a time and measuring the displacement that the knife or closure system can reach within the pre-defined starting time interval to determine the thickness and compressibility of the tissue encountered, or by pre-defining a constant force level and determining the time that is required to reach that force at a pre-defined speed or acceleration.

(465) Another method to accomplish control of energy modality is by using impedance measurements and force or velocity measures to correlate the density, conductivity and force resistance of the tissue to determine the type and thickness of the tissue as well as any irregularities that should impact rate of advance, wait, or energy density. Using combination of motor force closure measurements to determine if the jaw members of the end effector are closed on something that is likely to cause a short circuit (e.g., staple, clip, etc.) is also contemplated as is combining motor closure force with segmented flex force sensors that sense how much of the jaw member is filled in order to discriminate between large bites of softer tissue and smaller bites of harder tissue. For instance, the motor allows us new ways to determine if there is tissue or metal in the jaw members.

(466) FIG. 71 is a graphical representation **3700** of determining wait time based on tissue thickness. A first graph **3702** represents tissue impedance Z versus time (t) where the horizontal axis represents time (t) and the vertical axis represents tissue impedance Z . A second graph **3704** represents change in gap distance Δgap versus time (t) where the horizontal axis represents time (t) and the vertical axis represents change in gap distance Δgap . A third graph **3706** represents force F versus time (t) where the horizontal axis represents time (t) and the vertical axis represents force F . A constant force F applied to tissue and impedance Z interrogation define a wait period, energy modality (e.g., RF and ultrasonic) and motor control parameters. Displacement at a time provides velocity. With reference to the three graphs **3702**, **3704**, **3706**, impedance sensing energy is applied during a first period to determine the tissue type such as thin mesentery tissue (solid line), intermediate thickness vessel tissue (dashed line), or thick uterus/bowel tissue (dash-dot line).

(467) Using the thin mesentery tissue (solid line) as an example, as shown in the third graph **3706**, the clamp arm initially applies a force which ramps up from zero until it reaches a constant force **3724** at or about a first time t_1 . As shown in the first and second graphs **3702**, **3704**, from the time the clamp force is applied to the mesentery tissue until the first time t_1 , the gap distance Δgap curve **3712** decreases and the tissue impedance **3718** also decreases until the first time t_1 is reached. From the first time t_1 , a short wait period **3728** is applied before treatment energy, e.g.,

RF, is applied to the mesentery tissue at tE1. Treatment energy is applied for a second period **3710**, after which the tissue may be ready for a cut operation.

(468) As shown in the first and second graphs **3702**, **3704**, for intermediate thickness vessel tissue (dashed line), similar operations are performed. However, a medium wait period **3730** is applied before treatment energy is applied to the tissue at tE2.

(469) As shown in the first and second graphs **3702**, **3704**, for thick uterus/bowel tissue (dash-dot line), similar operations are performed. However, a long wait period **3726** is applied before treatment energy is applied to the tissue at tE3.

(470) Therefore, different wait periods may be applied based on the thickness of the tissue. The thickness of the tissue may be determined based on different gap distance behavior or impedance behavior before the time the constant force is reached. For example, as shown in the second graph **3704**, depending on the minimum gap distance reached when the constant force is reached, i.e., small gap, medium gap, or large gap, the tissue is determined as a thin tissue, an intermediate thickness tissue, or a thick tissue, respectively. As shown in the first graph **3702**, depending on the minimum impedance reached when the constant force is reached, e.g., small impedance, medium impedance, or large impedance, the tissue is determined as a thick tissue, an intermediate thickness tissue, or a thin tissue, respectively.

(471) Alternatively, as shown in the second graph **3704**, the thin tissue has a relatively steep gap distance slope, the intermediate thickness tissue has a medium gap distance slope, and the thick tissue has a relatively flat gap distance slope. As shown in the first graph **3702**, the thin tissue has a relatively flat impedance slope, and the intermediate thickness and thick tissues have relatively steep impedance slopes. Tissue thickness may be determined accordingly.

(472) The thickness of the tissue may also be determined as follows with reference to FIG. 72. FIG. 72 is a force versus time graph **3800** for thin, medium, and thick tissue types. The horizontal axis represents time (t) and the vertical axis represents force (F) applied by the clamp arm to the tissue. The graph **3800** depicts three curves, one for thin tissue **3802** shown in solid line, one for medium thickness tissue **3804** shown in dash-dot line, and one for thick tissue **3806** in dashed line. The graph **3800** depicts measuring time required to reach the preset force as an alternative to tissue gap to control delayed energy mode and other control parameters. Accordingly, the time to preset force **3808** for thick tissue **3806** is t1a, the time to preset force **3808** for medium thickness tissue **3804** is t1b, and the time to preset force **3808** for thin tissue **3802** is t1c.

(473) Once the force reaches the preset force **3808**, energy is applied to the tissue. For thin tissue **3802** the time to preset force $t1c > 0.5$ seconds, and then RF energy is applied for an energizing period of about 1-3 seconds. For thick tissue **3806** the time to preset force $t1a < 0.5$ seconds, and then RF energy is applied for an energizing period of about 5-9 seconds. For medium thickness tissue **3804** the time to preset force t1b is about 0.5 seconds and then RF energy is applied for an energizing period of about 3 to 5 seconds. These specific time periods may be adjusted without departing from the scope of the present disclosure.

(474) Alternatively, instead of predefining a constant force **3808**, a time period may be predefined. The force, gap distance, or impedance reached after the predefined time period may be measured, and may be used to determine the thickness of the tissue.

(475) The gap distance referred to in the above examples may be a gap distance between two jaws of an end effector of a surgical device. As discussed above, the gap distance may be measured with a rotary encoder attached to one or both of the jaws, or attached to a trigger used to operate the jaws.

(476) The force referred to in the above examples may be a force applied by one or both of the jaws on the tissue. As discussed above, the force may be measured using a current of a motor driving the jaws. Alternatively, the force may be measured directly using a force transducer.

(477) The impedance referred to in the above examples may be an impedance between the jaws across the tissue. The impedance may be measured using any conventional electrical techniques.

(478) FIG. 73 is a graph **3900** of motor current $I_{\text{sub.motor}}$ versus time t for different tissue types. Here, motor current $I_{\text{sub.motor}}$ may be a measure of force applied by one or both of the jaws on the tissue. A first curve **3910** shown in solid line is a motor current versus time curve for a thick tissue. A second curve **3920** shown in dashed line is a motor current versus time curve for a thin tissue. As shown by a first portion **3912** of the first curve **3910**, the motor current $I_{\text{sub.motor}}$ increases initially. Thereafter, as shown by a second portion **3914** (shadowed region) of the first curve **3910**, ultrasonic energy is applied, and the motor current $I_{\text{sub.motor}}$ decreases sharply. When the motor current decreases below a threshold **3930**, or when it reaches certain amount or certain percentage **3932** below the threshold **3930**, energy is switched from ultrasonic to RF. The switching may also occur when the slope of the motor current becomes relatively flat. As shown by a third portion **3916** of the first curve **3910**, RF energy is applied, and the motor current $I_{\text{sub.motor}}$ decreases slowly. In contrast, as shown in the second curve **3920** for a thin tissue, the motor current $I_{\text{sub.motor}}$ never increases beyond the threshold **3930**, and thus ultrasonic energy is not applied.

(479) FIG. 74 is a graphical depiction of impedance bath tub (e.g., the tissue impedance versus time initially decreases, stabilizes, and finally increases and the curve resembles a bath tub shape). A graph **4000** comprises three graphs **4002**, **4004**, **4006**, where the first graph **4002** represents RF power (P), RF voltage ($V_{\text{sub.RF}}$), and RF current ($I_{\text{sub.RF}}$) versus tissue impedance (Z), the second graph **4004** and third graph **4006** represent tissue impedance (Z) versus time (t). The first graph **4002** illustrates the application of power (P) for thick tissue impedance range **4010** and thin tissue impedance range **4012**. As the tissue impedance Z increases, the current $I_{\text{sub.RF}}$ decreases and the voltage $V_{\text{sub.RF}}$ increases. The power P increases until it reaches a maximum power output **4008**. When the RF power P is not high enough, for example as shown in the impedance range **4010**, RF energy may not be enough to treat tissues, therefore ultrasonic energy is applied instead.

(480) The second graph **4004** represents the measured tissue impedance Z versus time (t). The tissue impedance threshold limit **4020** is the cross over limit for switching between the RF and ultrasonic energy modalities. For example, as shown in the third graph **4006**, RF energy is applied while the tissue impedance is above the tissue impedance threshold limit **4020** and ultrasonic energy **4024** is applied while the tissue impedance is below the tissue impedance threshold limit **4020**. Accordingly, with reference back to the second graph **4004**, the tissue impedance of the thin tissue curve **4016** remains above the tissue impedance threshold limit **4020**, thus only RF energy modality is applied to the tissue. On the other hand, for the thick tissue curve **418**, RF energy modality is applied to the tissue while the impedance is above the tissue impedance threshold limit **4020** and ultrasonic energy is applied to the tissue when the impedance is below the tissue impedance threshold limit **4020**.

(481) Accordingly, the energy modality switches from RF to ultrasonic when the tissue impedance falls below the tissue impedance threshold limit **4020** and thus RF power P is low, and the energy modality switches from ultrasonic to RF when the tissue impedance rises above the tissue impedance threshold limit **4020** and thus RF power P is high enough. As shown in the third graph **4006**, the switching from ultrasonic to RF may be set to occur when the impedance reaches a certain amount or certain percentage above the threshold limit **4020**.

(482) Measurement of current, velocity, or torque of the motor related to the compression applied to the tissue can be used to change the impedance threshold that triggers the control of the treatment energy applied to the tissue. FIG. 75 illustrates a graph **4100** depicting one aspect of adjustment of energy switching threshold due to the measurement of a secondary tissue parameter such as continuity, temperature, pressure, and the like. The horizontal axis of the graph **4100** is time (t) and the vertical axis is tissue impedance (Z). The curve **4112** represents the change of tissue impedance (Z) over time (t) as different energy modalities are applied to the tissue. For example, the threshold may be adjusted depending on whether tissue is present at all parts of the jaws or present at only a portion of the jaws. Accordingly, once the tissue is located in particular segments

(zones) the control circuit in the generator adjusts the threshold accordingly. Reference is made to discussion below in connection with FIG. 80 for segmented measurement of tissue presence.

(483) As shown in FIG. 75, similar to the example described with reference to FIG. 74, the curve 4112 includes three separate sections 4106, 4108, 4110. The first section 4106 of the curve 4112 represents the time when RF energy is applied to the tissue until the tissue impedance drops below the adjusted threshold 4104. At that point 4114, the energy modality applied to tissue is changed from RF energy to ultrasonic energy. The ultrasonic energy is then applied in the second section 4108.

(484) Yet another embodiment of this concept may cause the wave shape to change in the RF signal based on the thickness measured by the force or force/position slope to determine whether to apply debulking or coagulation. For instance, sine wave or square waves are used to pre-heat the tissue and high voltage peak waves are used to coagulate the tissue.

(485) According to aspects of the present disclosure, a tissue short circuit condition may be detected. Detecting metal in the end effector (such as a staple or clip) avoid short circuits in the end effector that can divert current through the short circuit and render the RF therapy or sensing signal ineffective. A small piece of metal, such as a staple, can become quite hot with therapeutic RF current flowing through it. This could result in undesired effects in the tissue. Metal in contact with a vibrating ultrasonic blade can cause complications with the blade staying in resonance or possibly damage the blade or metal piece. Metal in the jaws can damage the pad that opposes a vibrating blade in the case of a clamped device. Metal can damage the closure mechanism due to over-stress of components while trying to close. Metal can damage a knife blade that may be forced to come in contact with the metal or attempt to cut through it.

(486) By using a motor, it is known (approximately) how open or closed the jaws are. If the jaws are open, the condition of how open or closed the jaws are can be identified in a variety of different methods—it could be the encoder count, the current going to the motor, a drop in motor voltage, etc. This can further be refined by looking at the derivative of either motor current or motor voltage. A short circuit is detected when the calculated impedance from the RF energy, is determined to be below a certain threshold. Due to cables and instrument design, this exact value varies. If the impedance is below or near this threshold, any of the following could aid in detecting a short circuit:

(487) Encoder count—if the jaws are still open, this implies there is tissue. If the impedance is at or below threshold, this is indicative that all energy is going through metal.

(488) Motor Current—if the motor has yet to detect its end of travel and it is experiencing high loads, the current increases (this is a method of force determination/calculation). As the current increases to a maximum, this coupled with the impedance measurement, could indicate a piece of metal is in the jaws. It takes more force to cut through a metal staple than it does of any tissue type. High current with low impedance (at or below threshold) implies possible short circuit.

(489) Motor Voltage—similar to the motor current example. If the motor current goes high and the encoder count slows down, the voltage decreases. Thus, it's possible that the motor voltage, coupled with impedance, could imply a short circuit.

(490) Derivative of Motor Current—this indicates the trend of the current, and is faster at predicting if the current is going to increase or decrease, based on previous performance. If the derivative of the current indicates more current will be going to the motor and the impedance is low, it is likely a short circuit.

(491) Derivative of Motor Voltage—this indicates the trend of the voltage, and is faster at predicting if the voltage is going to increase or decrease, based on previous performance. If the derivative of the voltage indicates less voltage will be going to the motor and the impedance is low, it is likely a short circuit.

(492) Combinations of the above are contemplated. In summary, a short circuit equation could be enhanced by monitoring any of the following conditions:

(493) Encoder Count+Impedance Encoder Count+Motor Current+Impedance Encoder Count+Motor Current+Motor Voltage+Impedance Encoder Count+Derivative of Motor Current+Motor Current+Impedance Encoder Count+Derivative of Motor Voltage+Motor Current+Impedance Motor Current+Impedance Motor Voltage+Impedance Derivative of Motor Current+Impedance Derivative of Motor Voltage+Impedance Encoder Count+Motor Voltage+Impedance Encoder Count+Derivative of Motor Current+Motor Voltage+Impedance Encoder Count+Derivative of Motor Voltage+Motor Voltage+Impedance Encoder Count+Derivative of Motor Current+Impedance Encoder Count+Derivative of Motor Current+Motor Voltage+Motor Current+Impedance Encoder Count+Derivative of Motor Voltage+Impedance Encoder Count+Derivative of Motor Voltage+Motor Voltage+Motor Current+Impedance

(494) Encoder Count+Derivative of Motor Voltage+Derivative of Motor Current+Motor Voltage+Motor Current+Impedance

(495) It is worthwhile noting that there are 5 separate conditions. This implies $2^{sup.5}=32$ different combinations of short circuit detection based on coupling impedance measurement to the 5 different conditions.

(496) FIG. 76 is a diagram of a process **4200** illustrating selective application of radio frequency or ultrasonic treatment energy based on measured tissue characteristics according to aspects of the present disclosure. One or more parameters, e.g., impedance, gap distance, force, temperature or their derivatives, may be measured **4210**. Based on the measured one or more parameters, one or more tissue characteristics, e.g., thickness, compressibility or short circuit condition may be determined **4220**. A controller of energy application may start application of RF or ultrasonic energy at a first time based at least in part on the one or more tissue characteristics **4230**.

Optionally, the controller may switch between RF and ultrasonic energy at a second time based at least in part on the one or more tissue characteristics **4240**. It should be noted that the measuring of the parameters **4210** and the determination of the tissue characteristics **4220** may occur during the application of energy **4230**, **4240**, and not necessarily prior to the application of energy **4230**, **4240**.

(497) According to aspects of the present disclosure, specific energy control algorithms can be employed. For instance, measuring the force of the user input on the energy activation control button can be utilized. The user control button may comprise a continuous measure button sensing that allows the device to set the on/off threshold as well as sense button degradation and user intensity. A force capacitive or resistive contact may be used that gives a continuous signal (not a interrupt/contact signal) which has a predefined force threshold which technique activate, a separate threshold meaning deactivate, and another intensity threshold above activate which indicates the need for a higher desired energy level. In one embodiment of this, the higher energy level could indicate the desire to activate both energy modalities simultaneously.

(498) Additionally or alternatively, a Hall sensor or other displacement based sensor on the energy activation button may also be utilized to get a continuous displacement of the button having a predefined activation position and a different energy deactivation threshold. In yet another embodiment, a control processor monitors the buttons use with a procedure and in-between procedures recording certain parameters of the button outputs, thereby allowing it to adjust the threshold to compensate for sensor wear and degradation, thus prolonging its useful life.

(499) In one aspect, the RF or ultrasonic energy may be terminated by the controller at a specific time. In some instances, the RF energy may desiccate the tissue to the point that application of ultrasonic energy comes too late to make a cut because the tissue is too dried out. For this type of event, the controller may be configured to terminate RF energy once a specific tissue impedance is met and going forward to apply only ultrasonic energy until the seal and cut is complete. For completeness, the present disclosure also contemplates terminating ultrasonic energy prior to terminating the RF energy to seal the tissue. Accordingly, in addition to switching between RF and ultrasonic energy, the present disclosure contemplates applying both RF and ultrasonic energy to

the tissue simultaneously to achieve a seal and cut. In other aspects, the present disclosure contemplates applying both RF and ultrasonic energy to the tissue simultaneously and then terminating the RF energy at a predetermined time. This may be advantageous, for example, to prevent the desiccating the tissue to a point that would render the application of ultrasonic energy ineffective for cutting tissue. In yet another aspect, the intensity of the RF energy may be reduced from a therapeutic level to a non-therapeutic level suitable for sensing during the sealing process to measure the tissue impedance, for example, using RF sensing without having an RF therapeutic effect on the tissue when this is desired.

(500) FIG. 77 is a graph 4300 depicting a relationship between trigger button displacement and sensor output. The vertical axis 4370 represents displacement of a trigger button. The trigger button, for example, may be located at a handle assembly or module and is used by a user to control application of RF and/or ultrasonic energy. The horizontal axis 4380 represents output of a displacement sensor, for example a Hall sensor. Shadowed zones 4350, 4360 represent out-of-bounds zones. As shown in the curve 4310 in FIG. 77, the sensor output is roughly proportional to the button displacement. A first zone 4320 may be an “OFF” zone, where button displacement is small and no energy is applied. A second zone 4330 may be an “ON” zone, where button displacement is medium and energy is applied. A third zone 4340 may be a “HIGH” zone, where button displacement is large and energy with high intensity is applied. Alternatively, the third zone 4340 may be a “HYBRID” zone, where both RF energy and ultrasonic energy are applied. Although the range of the sensor output is shown as 12V, any appropriate voltage range may be used.

(501) FIG. 78 is a graph 4400 depicting an abnormal relationship between trigger button displacement and sensor output. The vertical axis 4470 represents displacement of a trigger button. The horizontal axis 4480 represents output of a displacement sensor. A first curve 4410 represents a normal relationship between trigger button displacement and sensor output. A second curve 4420 represents an abnormal relationship between trigger button displacement and sensor output, where the sensor output does not reach its maximum value when the button is pressed all the way down. A third curve 4430 represents another abnormal relationship between trigger button displacement and sensor output, where the sensor output reaches its maximum value when the button is only pressed about half way. These abnormal situations may be detected during servicing or sterilization, and may indicate button wear or damage. Upon detection of these abnormal situations, the sensor may be recalibrated to compensate for the wear or damage.

(502) FIG. 79 is a graph A900 depicting an acceptable relationship between trigger button displacement and sensor output. The vertical axis 4570 represents displacement of a trigger button. The horizontal axis 4580 represents output of a displacement sensor. A first curve 4510 represents an as-manufactured relationship between trigger button displacement and sensor output. A second curve 4515 represents a changed relationship between trigger button displacement and sensor output due to aging. This relationship is acceptable because the user can still activate the three zones 4520, 4530, 4540.

(503) Another embodiment allows for local influencing of the RF power by using other local sensors within the flex circuit to either dampen power output or redirect power to another electrode. For instance, local measurement of temperature within a specific segmented electrode pair is used to influence the balance of power available to each side of the electrode pair. Local measurement of force is used to direct more power to the heavier loaded pairs of electrodes.

(504) FIG. 80 illustrates one aspect of a left-right segmented flexible circuit 4600. The left-right segmented flexible circuit 4600 comprises a plurality of segments L1-L5 on the left side of the left-right segmented flexible circuit 4600 and a plurality of segments R1-R5 on the right side of the left-right segmented flexible circuit 4600. Each of the segments L1-L5 and R1-R5 comprise temperature sensors and/or force sensors to sense tissue parameters locally within each segment L1-L5 and R1-R5. The left-right segmented flexible circuit 4600 is configured to influence the RF

treatment energy based on tissue parameters sensed locally within each of the segments L1-L5 and R1-R5.

(505) FIG. **81** is a cross-sectional view of one aspect of a flexible circuit **A1100** comprising RF electrodes and data sensors embedded therein. The flexible circuit **4700** can be mounted to the right or left portion of an RF clamp arm **A1102**, which is made of electrically conductive material such as metal. Below the RF clamp arm **4702**, down (vertical) force/pressure sensors **4706a**, **4706b** are embedded below a laminate layer **4704**. A transverse force/pressure sensor **4708** is located below the down (vertical) force/pressure sensor **4706a**, **4706b** layer and a temperature sensor **4710** is located below the transverse force/pressure sensor **4708**. An electrode **4712** is electrically coupled to the generator and configured to apply RF energy to the tissue **4714** located below the temperature sensor **4710**.

(506) FIG. **82** is a cross sectional view of an end effector **6200** comprising a jaw member **6202**, flexible circuits **6204a**, **6204b**, and segmented electrodes **6206a**, **6206b** provided on each flexible circuit **6204a**, **6204b**, according to one aspect of the present disclosure. FIG. **83** is a detailed view of the end effector **6200** shown in FIG. **82**, according to one aspect of the present disclosure. As previously discussed, it may be advantageous to provide general purpose controls on the primary handle assembly housing of the surgical instrument with dedicated shaft assembly controls located only on the shafts. For instance, an RF instrument may include a distal head rotation electronic rotary shaft control along with articulation buttons while the primary handle includes energy activation controls and jaw member clamp/unclamp trigger controls. In addition, sensors and end effector measurement elements can be employed. Segmented electrodes can be employed that allow for the instrument to sense where in the jaw members tissue is present. Such systems also may employ asymmetric flexible circuit electrodes that sense multiple tissue parameters and have built in electrodes as well as pressure elements for the measurement of pressure against the ultrasonic blade. These systems may also employ flex electrodes that allow a combo device to have sensors built into each of the two electrodes layered within the flex electrode stack.

(507) Turning now to FIGS. **82** and **83**, the end effector **6200** comprises a jaw member **6202**, flexible circuits **6204a**, **6204b**, and segmented electrodes **6206a**, **6206b** provided on each flexible circuit **6204a**, **6204b**. Each segmented electrode **6206a**, **6206b** comprises several segments. As shown, a first segmented electrode **6206a** comprises first and second segment electrode segments **6208a**, **6208b** and a second segmented electrode **6206b** comprises first and second segment electrode segments **6210a**, **6210b**. As shown particularly in FIG. **83** the jaw member **6202** is made of metal and conducts heat to maintain the jaw member **6202** cool. Each of the flexible circuits **6204a**, **6204b** comprises electrically conductive elements **6214a**, **6214b** made of metal or other electrical conductor materials and are electrically insulated from the metal jaw member **6202** by an electrically insulative laminate **6216**. The conductive elements **6214a**, **6214b** are coupled to electrical circuits located either in the shaft assembly, handle assembly, transducer assembly, or battery assembly of any one of the combination ultrasonic/electrosurgical instruments **500**, **600**, **700** described herein in connection with FIGS. **30-44**.

(508) FIG. **84A** is a cross sectional view of an end effector **6300** comprising a rotatable jaw member **6302**, a flexible circuit **6304**, and an ultrasonic blade **6306** positioned in a vertical orientation relative to the jaw member with no tissue located between the jaw member **6302** and the ultrasonic blade **6306**, according to one aspect of the present disclosure. FIG. **84B** is a cross sectional view of the end effector **6300** shown in FIG. **84A** with tissue **6308** located between the jaw member **6302** and the ultrasonic blade **6306**, according to one aspect of the present disclosure. The ultrasonic blade **6306** comprises side lobe sections **6310a**, **6310b** to enhance tissue dissection and uniform sections **6312a**, **6312b** to enhance tissue sealing. In the vertical orientation shown in FIGS. **84A** and **84B**, the ultrasonic blade **6308** is configured for tissue dissection.

(509) FIG. **85A** is a cross sectional view of the end effector **6300** shown in FIGS. **84A** and **84B** comprising a rotatable jaw member **6302**, a flexible circuit **6304**, and an ultrasonic blade **6306**

positioned in a horizontal orientation relative to the jaw member **6302** with no tissue located between the jaw member **6302** and the ultrasonic blade **6306**, according to one aspect of the present disclosure. FIG. **84B** is a cross sectional view of the end effector **6300** shown in FIG. **84A** with tissue **6308** located between the jaw member **6302** and the ultrasonic blade **6306**, according to one aspect of the present disclosure. In the horizontal orientation shown in FIGS. **85A** and **85B**, the ultrasonic blade **6308** is configured for tissue sealing (e.g., cauterization).

(510) With reference to FIGS. **84A-85B**, the flexible circuit **6304** includes electrodes configured to deliver high-frequency (e.g., RF) current to the tissue **6308** grasped between the jaw member **6302** and the ultrasonic blade **6306**. In one aspect, the electrodes may be segmented electrodes as described herein in connection with FIGS. **82-83** and **86-93**. The flexible circuit **6304** is coupled to a high-frequency (e.g., RF) current drive circuit **702** shown in connection with FIGS. **33-37**. In the illustrated example, the flexible circuit electrodes **6304** are coupled to the positive pole of the high-frequency (e.g., RF) current energy source and the ultrasonic blade **6306** is coupled to the negative (e.g., return) pole of the high-frequency (e.g., RF) current energy source. It will be appreciated that in some configurations, the positive and negative poles may be reversed such that the flexible circuit **6304** electrodes are coupled to the negative pole and the ultrasonic blade **6306** is coupled to the positive pole. The ultrasonic blade **6306** is acoustically coupled to an ultrasonic transducer **130**, **130'** as shown in connection with FIGS. **4-9**. In operation, the high-frequency (e.g., RF) current is employed to seal the tissue **6308** and the ultrasonic blade **6306** is used to dissect tissue using ultrasonic vibrations.

(511) In the example illustrated in FIGS. **784**, **84B**, **85A**, and **85B** the jaw member **6302** is rotatable about a stationary ultrasonic blade **6306**. The jaw member **6302** may rotate 90° relative to the ultrasonic blade **6306**. In another aspect, the jaw member **6302** may rotate greater than or equal to 360° relative to the ultrasonic blade **6306**. In various other aspects, the ultrasonic blade **6306** is rotatable about a stationary jaw member **6302**. The ultrasonic blade **6306** may rotate 90° relative to the jaw member **6302**. In another aspect, the ultrasonic blade **6306** may rotate greater than or equal to 360° relative to the jaw member **6302**.

(512) Turning now to FIG. **86**, the end effector **6400** comprises RF data sensors **6406**, **6408a**, **6408b** located on the jaw member **6402**. The end effector **6400** comprises a jaw member **6402** and an ultrasonic blade **6404**. The jaw member **6402** is shown clamping tissue **6410** located between the jaw member **6402** and the ultrasonic blade **6404**. A first sensor **6406** is located in a center portion of the jaw member **6402**. Second and third sensors **6408a**, **6408b** are located on lateral portions of the jaw member **6402**. The sensors **6406**, **6408a**, **6408b** are mounted or formed integrally with a flexible circuit **6412** (shown more particularly in FIG. **87**) configured to be fixedly mounted to the jaw member **6402**.

(513) The end effector **6400** is an example end effector for the surgical instruments **500**, **600**, **700** described herein in connection in FIGS. **30-44**. The sensors **6406**, **6408a**, **6408b** are electrically connected to a control circuit such as the control circuit **210** (FIG. **14**), **1300** (FIG. **62**), **1400** (FIG. **63**), **1500** (FIG. **64**) via interface circuits such as circuits **6550**, **6570** (FIGS. **96-97**), for example. The sensors **6406**, **6408a**, **6408b** are battery powered and the signals generated by the sensors **6406**, **6408a**, **6408b** are provided to analog and/or digital processing circuits of the control circuit.

(514) In one aspect, the first sensor **6406** is a force sensor to measure a normal force $F_{sub.3}$ applied to the tissue **6410** by the jaw member **6402**. The second and third sensors **6408a**, **6408b** include one or more elements to apply RF energy to the tissue **6410**, measure tissue impedance, down force $F_{sub.1}$, transverse forces $F_{sub.2}$, and temperature, among other parameters. Electrodes **6409a**, **6409b** are electrically coupled to an energy source such as the electrical circuit **702** (FIG. **34**) and apply RF energy to the tissue **6410**. In one aspect, the first sensor **6406** and the second and third sensors **6408a**, **6408b** are strain gauges to measure force or force per unit area. It will be appreciated that the measurements of the down force $F_{sub.1}$, the lateral forces $F_{sub.2}$, and the normal force $F_{sub.3}$ may be readily converted to pressure by determining the surface area upon

which the force sensors **6406**, **6408a**, **6408b** are acting upon. Additionally, as described with particularity herein, the flexible circuit **6412** may comprise temperature sensors embedded in one or more layers of the flexible circuit **6412**. The one or more temperature sensors may be arranged symmetrically or asymmetrically and provide tissue **6410** temperature feedback to control circuits of the ultrasonic drive circuit **177** and the RF drive circuit **702**.

(515) FIG. **87** illustrates one aspect of the flexible circuit **6412** shown in FIG. **86** in which the sensors **6406**, **6408a**, **6408b** may be mounted to or formed integrally therewith. The flexible circuit **6412** is configured to fixedly attach to the jaw member **6402**. As shown particularly in FIG. **87**, asymmetric temperature sensors **6414a**, **6414b** are mounted to the flexible circuit **6412** to enable measuring the temperature of the tissue **6410** (FIG. **86**).

(516) FIG. **88** is a cross-sectional view of the flexible circuit **6412** shown in FIG. **87**. The flexible circuit **6412** comprises multiple layers and is fixedly attached to the jaw member **6402**. A top layer of the flexible circuit **6412** is an electrode **6409a**, which is electrically coupled to an energy source such as the electrical circuit **702** (FIG. **34**) to apply RF energy to the tissue **6410** (FIG. **86**). A layer of electrical insulation **6418** is provided below the electrode **6409a** layer to electrically isolate the sensors **6414a**, **6406**, **6408a** from the electrode **6409a**. The temperature sensors **6414a** are disposed below the layer of electrical insulation **6418**. The first force (pressure) sensor **6406** is located below the layer containing the temperature sensors **6414a** and above a compressive layer **6420**. The second force (pressure) sensor **6408a** is located below the compressive layer **6420** and above the jaw member **6402** frame.

(517) FIG. **89** illustrates one aspect of a segmented flexible circuit **6430** configured to fixedly attach to a jaw member **6434** of an end effector. The segmented flexible circuit **6430** comprises a distal segment **6432a** and lateral segments **6432b**, **6432c** that include individually addressable sensors to provide local tissue control. The segments **6432a**, **6432b**, **6432c** are individually addressable to treat tissue and to measure tissue parameters based on individual sensors located within each of the segments **6432a**, **6432b**, **6432c**. The segments **6432a**, **6432b**, **6432c** of the segmented flexible circuit **6430** are mounted to the jaw member **6434** and are electrically coupled to an energy source such as the electrical circuit **702** (FIG. **34**) via electrical conductive elements **6436**. A Hall effect sensor **6438**, or any suitable magnetic sensor, is located on a distal end of the jaw member **6434**. The Hall effect sensor **6438** operates in conjunction with a magnet to provide a measurement of an aperture defined by the jaw member **6434**, which otherwise may be referred to as a tissue gap, as shown with particularity in FIG. **91**.

(518) FIG. **90** illustrates one aspect of a segmented flexible circuit **6440** configured to mount to a jaw member **6444** of an end effector. The segmented flexible circuit **6580** comprises a distal segment **6442a** and lateral segments **6442b**, **6442c** that include individually addressable sensors for tissue control. The segments **6442a**, **6442b**, **6442c** are individually addressable to treat tissue and to read individual sensors located within each of the segments **6442a**, **6442b**, **6442c**. The segments **6442a**, **6442b**, **6442c** of the segmented flexible circuit **6440** are mounted to the jaw member **6444** and are electrically coupled to an energy source such as the electrical circuit **702** (FIG. **34**), via electrical conductive elements **6446**. A Hall effect sensor **6448**, or other suitable magnetic sensor, is provided on a distal end of the jaw member **6444**. The Hall effect sensor **6448** operates in conjunction with a magnet to provide a measurement of an aperture defined by the jaw member **6444** of the end effector or tissue gap as shown with particularity in FIG. **91**. In addition, a plurality of lateral asymmetric temperature sensors **6450a**, **6450b** are mounted on or formally integrally with the segmented flexible circuit **6440** to provide tissue temperature feedback to control circuits in the ultrasonic drive circuit **177** and the RF drive circuit **702**.

(519) FIG. **91** illustrates one aspect of an end effector **6460** configured to measure a tissue gap GT. The end effector **6460** comprises a jaw member **6462** and a jaw member **6444**. The flexible circuit **6440** as described in FIG. **90**, is mounted to the jaw member **6444**. The flexible circuit **6440** comprises a Hall effect sensor **6448** that operates with a magnet **6464** mounted to the jaw member

6462 to measure the tissue gap GT. This technique can be employed to measure the aperture defined between the jaw member **6444** and the jaw member **6462**. The jaw member **6462** may be an ultrasonic blade.

(520) FIG. **92** illustrates one aspect of an end effector **6470** comprising segmented flexible circuit **6468** as shown in FIG. **80**. The end effector **6470** comprises a jaw member **6472** and an ultrasonic blade **6474**. The segmented flexible circuit **6468** is mounted to the jaw member **6472**. Each of the sensors disposed within the segments **1-5** are configured to detect the presence of tissue positioned between the jaw member **6472** and the ultrasonic blade **6474** and represent tissue zones **1-5**. In the configuration shown in FIG. **92**, the end effector **6470** is shown in an open position ready to receive or grasp tissue between the jaw member **6472** and the ultrasonic blade **6474**.

(521) FIG. **93** illustrates the end effector **6470** shown in FIG. **92** with the jaw member **6472** clamping tissue **6476** between the jaw member **6472** and the ultrasonic blade **6474**. As shown in FIG. **93**, the tissue **6476** is positioned between segments **1-3** and represents tissue zones **1-3**. Accordingly, tissue **6476** is detected by the sensors in segments **1-3** and the absence of tissue (empty) is detected in section **6478** by segments **4-5**. The information regarding the presence and absence of tissue **6476** positioned within certain segments **1-3** and **4-5**, respectively, is communicated to a control circuit such as the control circuits **210** (FIG. **14**), **1300** (FIG. **62**), **1400** (FIG. **63**), **1500** (FIG. **64**) via interface circuits such as circuits **6550**, **6570** (FIGS. **96-97**), for example. The control circuit is configured to energize only the segments **1-3** where tissue **6476** is detected and does not energize the segments **4-5** where tissue is not detected. It will be appreciated that the segments **1-5** may contain any suitable temperature, force/pressure, and/or Hall effect magnetic sensors to measure tissue parameters of tissue located within certain segments **1-5** and electrodes to deliver RF energy to tissue located in certain segments **1-5**.

(522) FIG. **94** illustrates graphs **6480** of energy applied by the right and left side of an end effector based on locally sensed tissue parameters. As discussed herein, the jaw member of an end effector may comprise temperature sensors, force/pressure sensors, Hall effect sensors, among others, along the right and left sides of the jaw member. Thus, RF energy can be selectively applied to tissue positioned between the clam jaw and the ultrasonic blade. The top graph **6482** depicts power PR applied to a right side segment of the jaw member versus time (t) based on locally sensed tissue parameters. Thus, the control circuit such as the control circuits **210** (FIG. **14**), **1300** (FIG. **62**), **1400** (FIG. **63**), **1500** (FIG. **64**) via interface circuits such as circuits **6550**, **6570** (FIGS. **96-97**), for example, is configured to measure the sensed tissue parameters and to apply power PR to a right side segment of the jaw member. The RF drive circuit **702** (FIG. **34**) delivers an initial power level $P_{sub.1}$ to the tissue via the right side segment and then decreases the power level to $P_{sub.2}$ based on local sensing of tissue parameters (e.g., temperature, force/pressure, thickness) in one or more segments. The bottom graph **6484** depicts power $P_{sub.L}$ applied to a left side segment of the jaw member versus time (t) based on locally sensed tissue parameters. The RF drive circuit **702** delivers an initial power level of $P_{sub.1}$ to the tissue via the left side segment and then increases the power level to $P_{sub.3}$ based on local sensing of tissue parameters (e.g., temperature, force/pressure, thickness). As depicted in the bottom graph **6484**, the RF drive circuit **702** is configured to re-adjust the energy delivered $P_{sub.3}$ based on sensing of tissue parameters (e.g., temperature, force/pressure, thickness).

(523) FIG. **95** is a cross-sectional view of one aspect of an end effector **6530** configured to sense force or pressure applied to tissue located between a jaw member and an ultrasonic blade. The end effector **6530** comprises a clamp jaw **6532** and a flexible circuit **6534** fixedly mounted to the jaw member **6532**. The jaw member **6532** applies forces $F_{sub.1}$ and $F_{sub.2}$ to the tissue **6536** of variable density and thickness, which can be measure by first and second force/pressure sensors **6538**, **6540** located in different layers of the flexible circuit **6534**. A compressive layer **6542** is sandwiched between the first and second force/pressure sensors **6538**, **6540**. An electrode **6544** is located on outer portion of the flexible circuit **6534** which contacts the tissue. As described herein,

other layers of the flexible circuit **6534** may comprise additional sensors such temperature sensors, thickness sensors, and the like.

(524) FIGS. **96-97** illustrate various schematic diagrams of flexible circuits of the signal layer, sensor wiring, and an RF energy drive circuit. FIG. **96** is a schematic diagram of one aspect of a signal layer of a flexible circuit **6550**. The flexible circuit **6550** comprises multiple layers (~4 to ~6, for example). One layer will supply the integrated circuits with power and another layer with ground. Two additional layers will carry the RF power RF1 and RF2 separately. An analog multiplexer switch **6552** has eight bidirectional translating switches that can be controlled through the I.sup.2C bus to interface to the control circuit **210** (FIG. **14**) via the SCL-C/SDA-C interface channel. The SCL/SDA upstream pair fans out to eight downstream pairs, or channels. Any individual SCn/SDn channel or combination of channels can be selected, determined by the contents of a programmable control register. There are six down stream sensors, three on each side of the jaw member. A first side **6554a** comprises a first thermocouple **6556a**, a first pressure sensor **6558a**, and a first Hall effect sensor **6560a**. A second side **6554b** comprises a second thermocouple **6556b**, a second pressure sensor **6558b**, and a second Hall effect sensor **6560b**. FIG. **97** is a schematic diagram **6570** of sensor wiring for the flexible circuit **6550** shown in FIG. **96** to the switch **6552**.

(525) FIG. **98A** illustrates an end effector **6670** comprising a jaw member **6672** and an ultrasonic blade **6674**, where the jaw member **6672** includes electrodes **6676**. The end effector **6670** can be employed in one of the surgical instruments combination ultrasonic/electrosurgical instruments **500, 600, 700** described herein in connection with FIGS. **30-44**, where the combination ultrasonic/electrosurgical instruments **500, 600, 700** are configured to switch between RF, ultrasonic, and combination RF/ultrasonic energy automatically based on a sensed/calculated measure of device parameters such as, for example, impedance, current from the motor, jaw member gap, tissue compression, temperature, among others, implying tissue thickness and/or type. Referring to FIG. **98A**, the end effector **6670** may be positioned by a physician to surround tissue **6678** prior to compression, cutting, or stapling. As shown in FIG. **98A**, no compression may be applied to the tissue while preparing to use the end effector **6670**. As shown in FIG. **98A**, the tissue **6678** is not under compression between the jaw member **6672** and the ultrasonic blade **6674**.

(526) Referring now to FIG. **98B**, by engaging the trigger on the handle of a surgical instrument, the physician may use the end effector **6670** to compress the tissue **6678**. In one aspect, the tissue **6678** may be compressed to its maximum threshold, as shown in FIG. **98B**. As shown in FIG. **98A**, the tissue **6678** is under maximum compression between the jaw member **6672** and the ultrasonic blade **6674**.

(527) Referring to FIG. **99A**, various forces may be applied to the tissue **6678** by the end effector **6670**. For example, vertical forces F1 and F2 may be applied by the jaw member **6672** and the ultrasonic blade **6674** of the end effector **6670** as tissue **6678** is compressed between the two. Referring now to FIG. **99B**, there is shown various diagonal and/or lateral forces also may be applied to the tissue **6678** when compressed by the end effector **6670**. For example, a force F3 may be applied. For the purposes of operating the combination ultrasonic/electrosurgical instruments **500, 600, 700** (FIGS. **30-44**), it may be desirable to sense or calculate the various forms of compression being applied to the tissue by the end effector. For example, knowledge of vertical or lateral compression may allow the end effector to more precisely or accurately apply a staple operation or may inform the operator of the surgical instrument such that the surgical instrument can be used more properly or safely.

(528) In one form, a strain gauge can be used to measure the force applied to the tissue **6678** by the end effector shown in FIGS. **98A-B, 99A-B**. A strain gauge can be coupled to the end effector **6670** to measure the force on the tissue **6678** being treated by the end effector **6670**. With reference now also to FIG. **100**, in the aspect illustrated in FIG. **100**, a system **6680** for measuring forces applied to the tissue **6678** comprises a strain gauge sensor **6682**, such as, for example, a micro-strain gauge,

is configured to measure one or more parameters of the end effector **6670** such as, for example, the amplitude of the strain exerted on a jaw member of an end effector, such as the jaw member **6672** of FIGS. **99A-B**, during a clamping operation, which can be indicative of the tissue compression. The measured strain is converted to a digital signal and provided to a processor **6690** of a microcontroller **6688**. A load sensor **6684** can measure the force to operate the ultrasonic blade **6674** to cut the tissue **6678** captured between the jaw member **6672** and the ultrasonic blade **6674** of the end effector **6670**. A magnetic field sensor **6686** can be employed to measure the thickness of the captured tissue **6678**. The measurement of the magnetic field sensor **6686** also may be converted to a digital signal and provided to the processor **6690**.

(529) Further to the above, a feedback indicator **6694** also can be configured to communicate with the microcontroller **6688**. In one aspect, the feedback indicator **6694** can be disposed in the handle of the combination ultrasonic/electrosurgical instruments **500, 600, 700** (FIGS. **30-44**).

Alternatively, the feedback indicator **6694** can be disposed in a shaft assembly of a surgical instrument, for example. In any event, the microcontroller **6688** may employ the feedback indicator **6694** to provide feedback to an operator of the surgical instrument with regard to the adequacy of a manual input such as, for example, a selected position of a firing trigger that is used to cause the end effector to clamp down on tissue. To do so, the microcontroller **6688** may assess the selected position of the jaw member **6672** and/or firing trigger. The measurements of the tissue **6678** compression, the tissue **6678** thickness, and/or the force required to close the end effector **6670** on the tissue, as respectively measured by the sensors **6682, 6684, 6686**, can be used by the microcontroller **6688** to characterize the selected position of the firing trigger and/or the corresponding value of the speed of end effector. In one instance, a memory **6692** may store a technique, an equation, and/or a look-up table which can be employed by the microcontroller **6688** in the assessment.

(530) In view of the above, in one aspect the present disclosure provides a surgical instrument comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft, the end effector comprising a first jaw and a second jaw configured for pivotal movement between a closed position and an open position; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle assembly; a radio frequency (RF) energy output powered by the battery assembly and configured to apply RF energy to a tissue; an ultrasonic energy output powered by the battery assembly and configured to apply ultrasonic energy to the tissue; and a controller configured to, based at least in part on a measured tissue characteristic, start application of RF energy by the RF energy output or application of ultrasonic energy by the ultrasonic energy output at a first time.

(531) In one aspect, the controller may be further configured to, based at least in part on the measured tissue characteristic, switch between RF energy applied by the RF energy output and ultrasonic energy applied by the ultrasonic energy output at a second time. The controller may be further configured to, based at least in part on the measured tissue characteristic, terminate the RF energy applied by the RF energy output after a first period and apply only ultrasonic energy by the ultrasonic energy output for a second period. The controller may be further configured to, based at least in part on the measured tissue characteristic, terminate the ultrasonic energy applied by the ultrasonic energy output after a first period and apply only RF energy by the RF energy output for a second period second time. The controller may be further configured to, based at least in part on the measured tissue characteristic, control a level of RF energy applied by the RF energy output or ultrasonic energy applied by the ultrasonic energy output. The controller may be further configured to, based at least in part on the measured tissue characteristic, reduce a level of RF energy applied by the RF energy output from a therapeutic energy level to a non-therapeutic energy level suitable for measuring tissue impedance without a therapeutic effect on the tissue. The controller may be further configured to, based at least in part on the measured tissue characteristic, control a waveform of RF energy applied by the RF energy output or ultrasonic energy applied by the

ultrasonic energy output. The controller may be further configured to determine the measured tissue characteristic based on behavior of impedance between the first and second jaws across the tissue.

(532) The controller may be further configured to determine the measured tissue characteristic based on behavior of a gap distance between the first and second jaws. The controller may be further configured to determine the measured tissue characteristic based on behavior of a force applied by one or both of the first and second jaws on the tissue. The force may be measured by a current or voltage of a motor driving one or both of the first and second jaws.

(533) The controller may be further configured to determine the measured tissue characteristic based on a time required to reach a constant force. The measured tissue characteristic may be tissue thickness. For a thick tissue, the first time may be determined to be a long delay after a force applied by one or both of the first and second jaws on the tissue has reached a constant force and for a thin tissue, the first time may be determined to be a short delay after the force has reached the constant force. For a thick tissue, RF energy may be applied before and after a first period, where impedance between the first and second jaws across the tissue may be below a first impedance threshold and ultrasonic energy is applied. For a thin tissue, only RF energy may be applied.

(534) The controller may be further configured to adjust the first impedance threshold based on a secondary tissue characteristic different from the measured tissue characteristic. For a thick tissue, ultrasonic energy may be switched to RF energy when a force applied by one or both of the first and second jaws on the tissue falls below a first force threshold, for a thin tissue, only RF energy may be applied. The measured tissue characteristic may be tissue compressibility. The measured tissue characteristic may be tissue short circuit condition.

(535) The controller may be further configured to determine that there is a tissue short circuit condition when impedance between the first and second jaws across the tissue is below a second impedance threshold, and a gap distance between the first and second jaws is above a gap distance threshold. The controller may be further configured to determine that there is a tissue short circuit condition when impedance between the first and second jaws across the tissue is below a third impedance threshold, and a force applied by one or both of the first and second jaws on the tissue is above a second force threshold.

(536) In another aspect, the present disclosure provides a method for operating a surgical instrument, the surgical instrument comprising a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft, the end effector comprising a first jaw and a second jaw configured for pivotal movement between a closed position and an open position, a handle assembly coupled to a proximal end of the shaft, and a battery assembly coupled to the handle assembly, the method comprising: measuring a tissue characteristic; and starting, based at least in part on the measured tissue characteristic, application of RF energy by a RF energy output or application of ultrasonic energy by a ultrasonic energy output at a first time. The method may further comprise switching, based at least in part on the measured tissue characteristic, between RF energy applied by the RF energy output and ultrasonic energy applied by the ultrasonic energy output at a second time.

(537) In another aspect, the present disclosure provides a surgical instrument comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft, the end effector comprising a first jaw and a second jaw configured for pivotal movement between a closed position and an open position; a handle assembly coupled to a proximal end of the shaft, the handle assembly comprising a button configured to be displaced when pressed by a user; a battery assembly coupled to the handle assembly; a sensor configured to measure a displacement or intensity of the button; a radio frequency (RF) energy output powered by the battery assembly and configured to apply RF energy to a tissue; an ultrasonic energy output powered by the battery assembly and configured to apply ultrasonic energy to the tissue; and a controller configured to: control the RF energy output to apply RF energy or control the ultrasonic energy output to apply

ultrasonic energy at a low level when the displacement or intensity measured by the sensor is above a first threshold but below a second threshold higher than the first threshold, and control the RF energy output to apply RF energy or control the ultrasonic energy output to apply ultrasonic energy at a high level when the displacement or intensity measured by the sensor is above the second threshold.

(538) The sensor may be a Hall sensor. The sensor may be configured to measure force applied to the button and the displacement or intensity of the button is the force applied to the button. The sensor may be configured to be calibrated after the surgical instrument is manufactured, such that an output of the sensor is substantially proportional to the displacement or intensity of the button. The sensor may be configured to be calibrated if the output of the sensor reaches maximum when the displacement or intensity of the button has not reached maximum. The sensor may be configured to be calibrated if the displacement or intensity of the button reaches maximum when the output of the sensor has not reached maximum.

(539) In another aspect, the present disclosure provides a surgical instrument comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft, the end effector comprising a first jaw and a second jaw configured for pivotal movement between a closed position and an open position; a handle assembly coupled to a proximal end of the shaft, the handle assembly comprising a button configured to be displaced when pressed by a user; a battery assembly coupled to the handle assembly; a sensor configured to measure a displacement or intensity of the button; a radio frequency (RF) energy output powered by the battery assembly and configured to apply RF energy to a tissue; an ultrasonic energy output powered by the battery assembly and configured to apply ultrasonic energy to the tissue; and a controller configured to: control the RF energy output to apply RF energy or control the ultrasonic energy output to apply ultrasonic energy when the displacement or intensity measured by the sensor is above a first threshold but below a second threshold higher than the first threshold, and control the RF energy output to apply RF energy and control the ultrasonic energy output to apply ultrasonic energy when the displacement or intensity measured by the sensor is above the second threshold.

(540) The sensor may be a Hall sensor. The sensor may be configured to be calibrated after the surgical instrument is manufactured, such that an output of the sensor is substantially proportional to the displacement or intensity of the button. The sensor may be configured to be calibrated after the surgical instrument is manufactured, such that an output of the sensor is substantially proportional to the displacement or intensity of the button. The sensor may be configured to be calibrated if the displacement or intensity of the button reaches maximum when the output of the sensor has not reached maximum.

(541) In another aspect, the present disclosure provides a surgical instrument comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft, the end effector comprising a first jaw and a second jaw configured for pivotal movement between a closed position and an open position, wherein the first or second jaw comprising: a first sensor configured to measure a tissue characteristic at a first location, and a second sensor configured to measure the tissue characteristic at a second location; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle assembly; a radio frequency (RF) energy output powered by the battery assembly and configured to apply RF energy to a tissue; an ultrasonic energy output powered by the battery assembly and configured to apply ultrasonic energy to the tissue; and a controller configured to, based at least in part on the measured tissue characteristic at the first location and the second location, control the RF energy output to apply RF energy or control the ultrasonic energy output to apply ultrasonic energy.

(542) The first and second sensors may be vertical pressure sensors. The controller may be further configured to: apply high energy at a location with high sensor output; and apply low energy at a location with low sensor output. The first and second sensors may be transverse pressure sensors. The first and second sensors may be temperature sensors. The first and second sensors may be

configured to sense presence or absence of tissue at the first location and the second location.

(543) The controller may be further configured to: set a first impedance threshold below which RF energy is switched to ultrasonic energy when tissue is present at both the first location and the second location; and set a second impedance threshold below which RF energy is switched to ultrasonic energy when tissue is present at only one of the first location and the second location, wherein the first and second impedance thresholds are different. The controller may be further configured to: set a first force threshold used to control application of energy when tissue is present at both the first location and the second location; and set a second force threshold used to control application of energy when tissue is present at only one of the first location and the second location, wherein the first and second force thresholds are different. The controller may be further configured to: apply energy at a location where tissue is present; and not apply energy at a location where tissue is absent.

Modular Battery Powered Handheld Surgical Instrument with Variable Motor Control Limits, Motor Control Limit Profile, and Motor Control Limits Based on Tissue Characterization

(544) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with variable motor control limits. Disclosed is a surgical instrument that includes a shaft assembly; a handle assembly; a battery assembly; a first driver configured to drive movement of at least a first component of the surgical instrument; a second driver configured to drive movement of at least a second component of the surgical instrument; a motor powered by the battery assembly and configured to selectively actuate the first driver or the second driver using an output of the motor; and a controller for the motor, configured to: perform a first limiting operation to the output of the motor when the motor actuates the first driver and a first limiting condition is met, and perform a second limiting operation to the output of the motor when the motor actuates the second driver and a second limiting condition is met.

(545) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with motor control limit profile. Disclosed is a surgical instrument that includes a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle assembly; a driver configured to drive movement of at least one component of the surgical instrument; a motor powered by the battery assembly and configured to actuate the driver using an output of the motor; and a controller for the motor, configured to perform a first limiting operation to the output of the motor when a first limiting condition is met, wherein the first limiting condition defines a maximum control variable profile of the motor over a range of the movement of the at least one component.

(546) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with motor control limits based on tissue characterization. A surgical instrument comprises a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle assembly; a driver configured to drive movement of at least one component of the surgical instrument; a motor powered by the battery assembly and configured to actuate the driver using an output of the motor; and a controller for the motor, configured to perform a limiting operation to the output of the motor when a limiting condition is met, wherein the limiting condition is determined based at least in part on a tissue characteristic.

(547) FIGS. **101-84** illustrate various aspects of the present disclosure that is directed to motor and a motor controller where a first limiting threshold is used on the motor for the purpose of attaching a modular assembly and a second threshold associated with a second assembly step or functionality of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-70**. According to various aspects of the present disclosure, a system includes a motor **4830, 1160, 1432** (FIGS. **103, 49, and 63**, respectively), a motor controller (e.g., motor control circuits **726** shown in FIG. **36**, motor drive circuits **1165, 4982** shown in FIGS. **50**

and **80**, respectively, as well as the motor control circuit **1430** and primary processor **1302** as shown in FIG. **63**), a first controller limiting threshold associated to an attached assembly or function step of operation and a second threshold associated with another assembly or function step. The first threshold is applied when its system is in operation, and the second threshold is used as opposed to the first if a second assembly is coupled or in operation. One way to enable this functionality is by having a multi-purpose motor that actuates both transducer torqueing onto the handpiece, articulation control and clamp arm control, where the torqueing of transducer has a different limit than the articulation limit and both are different from the clamp arm limit. Different control responses can also be created when the system exceeds the motor current threshold, where this threshold can be based, in part, on the mechanism function or longitudinal position of specific components in the system.

(548) FIG. **101** is a graph **4800** showing a limiting operation on a torque applied to an ultrasonic transducer **130**, **130'** as described herein in connection with FIGS. **4-10B**. The horizontal axis represents time (t), and the vertical axis represents torque (T). The ultrasonic transducer may be used by a surgical instrument to apply ultrasonic vibrational energy to tissue. The torque applied to the ultrasonic transducer may be measured by measuring the motor load current of the motor **4830** (FIG. **73**) driving (e.g., torqueing) the ultrasonic transducer. As shown in graph **4800**, the torque applied to the ultrasonic transducer increases over time until the torque reaches a predetermined torque limit **4804** at a time **4802**. At that time **4802**, the motor is cut off to reduce the torque to zero. Therefore, an electronic current limiter limits the torque to a known force.

(549) FIG. **102** is a graph **4810** comparing different limiting conditions and different limiting operations when the motor is driving different moving components. The horizontal axis represents time (t), and the vertical axis represents motor current (I). Motor current may be an indication of force or torque output by the motor. In some aspects, a single motor may selectively actuate different drivers for driving torque on a transducer **4812**, user activated distal head rotation **4814**, articulation **4816**, or clamp arm movement **4818**, among others. Articulation **4816** as used herein may be articulation movement of two portions of the shaft about an articulation joint coupled therebetween. Distal head rotation **4814** as used herein may be axial rotation of the distal one of the two portions. Clamp arm movement **4818** as used herein may be pivotal movement of two jaws (clam arms) of an end effector of a surgical instrument between a closed position and an open position.

(550) As shown in graph **4810**, torque on transducer **4812** has a first current limit **4822**, distal head rotation **4814** has a second current limit **4820**, articulation **4816** has a third current limit **4826**, clamp arm movement has a fourth current limit **4824**, and so on. When torque on transducer **4812**, distal head rotation **4814** or articulation **4816** reaches their respective current limits **4822**, **4820**, **4826**, the motor is cut off completely (e.g., safety limits). In contrast, when clamp arm movement **4818** reaches its current limit **4824**, the current is maintained at a value below or about the current limit **4824**, not completely cut off (e.g., constant force limit). It will be appreciated that in various aspects a controller for the motor may be configured to perform limiting operations to the output of the motor when a first limiting condition is met. In one aspect, the limiting condition defines a maximum control variable profile of the motor over a range of the movement of the at least one component. In one aspect, the control variable profile is a current profile of the motor. In another aspect, the variable profile is a voltage profile of the motor. In other aspects, the control variable profile of the motor may be power profile of the motor, a torque profile of the motor, or pother profiles of the motor. In other aspects, the control variable profile is position profile, inertia profile, velocity profile, or acceleration profile, either of the motor or an element coupled to the shaft of the motor.

(551) FIG. **103** is a perspective view of a motor **4830** comprising a strain gauge **4834** used for measuring torque. The motor **4830** comprises planetary gear **4832** in its body, and comprises a pair of fixed magnets **4836**, **4838**, a coiled wire **4840** and the strain gauge **4834** (and its microchip) on

the output shaft of the motor **4830**. The coiled wire **4840** rotates to power the strain gauge **4834**. Therefore, the torque applied to the transducer can be directly measured, instead of being measured using the motor current. The coiled wire **4840** generates an electric current as it rotates through the magnetic field produced by the pair of magnets **4836**, **4838**.

(552) In another aspect of the present disclosure, the rate of change of the user trigger position is used to influence the motor control parameters. For instance, if the user is making many opposing trigger motions, implying fine dissection or precision, the system runs potentially different maximum thresholds as well as dampened acceleration and velocity direction to the motor **4830** to smooth out fine movement of the jaw members. Alternatively, a minimum trigger motion can be used to indicate a desired motion of the jaw member based on the time between larger motions, allowing the motor controller to remove hand tremor or other undesired motions to powered jaw motion.

(553) FIG. **104** are graphs **4850** and **4860** showing smoothing out of fine trigger button movement by a motor controller. A first graph **4850** of FIG. **104** shows displacement of a trigger button over time, and a second graph **4860** of FIG. **104** shows velocity of movement over time. The trigger button, for example, may be located at a handle assembly or module and is used by a user to control jaw member opening or closing. As shown in the first graph **4850**, a first trigger button movement **4852** is manifested as a high frequency and/or low magnitude movement over a period T1, which may indicate user hand tremor. A second trigger button movement **4854**, **4864** is a low frequency and/or high magnitude movement over a period T2, which may indicate intentional movement. Therefore, when the motor controller translates the trigger button movement to velocity of jaw member opening/closing, the motor controller may perform a proportional adjustment on the first trigger button movement **4852**, thus forming a smooth portion **4862** of velocity curve. For the intentional movement **4854**, no smoothing operation is performed.

(554) In another aspect of the present disclosure, a system includes a motor **4830** (FIG. **103**) to actuate a mechanism, a motor controller to control the motor velocity or torque, where measurement of current or a parameter related to current through the motor **4830** is used to control the motor **4830**. A non-linear threshold is used to trigger motor **4830** adjustments at different magnitudes based on position, inertia, velocity, or acceleration. For instance, upper and lower current thresholds could be employed to set a bounded pressure range for the clamp arm to provide the motor control circuit an operational range including mechanical advantage adjustments for the mechanism. Another version of this is where the I-blade radial threshold force limit is based on the system mechanical advantage and advancement stroke location of the I-blade.

(555) Yet another version is where the slope rise or fall of current or voltage is used to provide a forecasting element to determine if they will likely exceed the threshold, and is subsequently used to vary the threshold limit. For instance, tissue compressibility used in conjunction with motor current rise could be used to provide a calculation of the maximum force expected on the components, based on the current location of closure mechanism in relation to full closure.

(556) In still another example, position measurement of an actuated body is performed and the adjustment of the rate of change of the actuation is based on its position within its overall stroke. For instance, the clamp arm is allowed to make large acceleration and velocity changes when between 95% and 25% of its overall limits, but it must run within a much slower speed when outside of this range. At 95% of stroke (which may be considered fully open) the mechanism is approaching its max open condition, and in order to limit overstress on its mechanical stops the system begins to slow down and limit speed/torque. At 25% the jaws are in contact with tissue or approaching contact with tissue, so the system begins to limit acceleration and speed in order to soften its handling of tissue and minimize tearing. Also, each of the powered capabilities being run by the same motor **4830** could have differing limits indicating acceleration or velocity limits based on being calibrated or based on the inertia and frictional needs of the system. For instance, heavier systems have more constraining limits than lighter systems which are easier to start and stop.

(557) FIG. 105 is a graph 4870 showing a non-linear force limit 4872 and corresponding velocity adjustment for I-blade RF motor 4830 control, where F represents force and V represents velocity. As shown in FIG. 105, the non-linear force limit 4872 sets a lower force limit at both ends of the range of movement δ and a higher force limit in the middle of the range of movement δ . In the beginning, a relatively high velocity 4884 is applied, and the force 4874 on the I-blade increases rapidly. At a first point 4878 in the range of movement, the force 4874 exceeds the force limit 4872, thus the velocity is reduced accordingly to a medium velocity 4886. Therefore, the force 4874 gradually falls back below the force limit 4872. When the force 4874 exceeds the force limit 4872 again at a second point 4880 in the range of movement, the velocity is further reduced to a relatively low velocity 4888. Therefore, the force 4874 gradually falls back below the force limit 4872 again. A dash dot force curve 4876 shows the ideal behavior of the force on the I-blade (ideal tissue compression limit).

(558) FIG. 106 is a graph 4890 showing force limits 4896, 4898 and corresponding velocity adjustments for jaw motor control. As shown in FIG. 106, an upper force limit 4896 and a lower force limit 4898 are provided for the force (pressure) applied by the jaws on the tissue. In the beginning of the range of jaw movement δ , the force (F) 4892 and the velocity (V) 4894 both increase. At a first point $\delta 1$ in the range of movement, the force enters the region between the upper and lower limits 4896, 4898. Thereafter the velocity is set to be a constant velocity. At a second point $\delta 2$ in the range of movement, the force exceeds the upper limit 4896. Thereafter the constant velocity is lowered, and the force falls back under the upper limit 4896. At a third point $\delta 3$ in the range of movement, the force falls under the lower limit 4898. Thereafter the constant velocity is raised, and the force increases to above the lower limit 4898. At a fourth point $\delta 4$ in the range of movement, the force exceeds the upper limit 4896. Thereafter the velocity is lowered, and the force falls back under the upper limit 4896. Because the rate of decrease of the force is relatively high, a linearly increasing velocity instead of constant force is applied between the fourth point $\delta 4$ and a fifth point $\delta 5$, where the force falls below the lower limit 4898. Repeated description of the remaining operations is omitted. When the rate of decrease of the force is relatively high, an increasing velocity is applied. When the rate of increase of the force is relatively high, a decreasing velocity is applied. Therefore, a forecast is provided to control the velocity before the force moves outside the permitted range.

(559) FIG. 107 are graphs 4900, 4910 showing different velocity limits when the motor 4830 is driving different moving components. As shown in a first graph 4900 of FIG. 107, a higher velocity limit 4902 is set for jaw clamping, and a lower velocity limit 4906 is set for articulation. A solid curve 4904 represents the opening and closing of jaw members, and its velocity does not exceed the higher velocity limit 4902. A dashed curve 4908 represents articulation, and its velocity does not exceed the lower velocity limit 4906.

(560) As shown in a second graph 4910 of FIG. 107, jaw clamping 4912 may have a different full velocity range than articulation 4920. Jaw clamping 4912 has two limited velocity zones 4914, 4916 at both ends of the range of movement, and a full velocity zone 4918 in the middle of the range of movement (e.g., 10% to 95% of the range of movement). Articulation 4920 has two limited velocity zones 4922, 4924 at both ends of the range of movement, and a full velocity zone 4926 in the middle of the range of movement (e.g., 25% to 75% of the range of movement). The full velocity zone of jaw clamping 4918 has a larger range than the full velocity zone of articulation 4926. The reason may be that articulation is a heavier system and needs a larger range to start and stop.

(561) FIG. 108 is a graph 4950 showing velocity limits 4952, 4954 at the beginning and the end of the range of movement. As shown in FIG. 108, at one end of the range of movement δ (e.g., when jaws are approaching tissue), a first velocity limit 4952 may be set for the jaw movement in a range of, e.g., 10 degrees. At the other end of the range of movement δ (e.g., when jaws are approaching mechanical stop), a second velocity limit 4954 may be set for the jaw movement in a range of, e.g.,

5 degrees. As shown in FIG. 108, the force limits described with reference to FIG. 106 may be used in conjunction with the velocity limits described with reference to FIG. 108.

(562) FIG. 109 are diagrams 4960, 4970 showing velocity limits at the beginning and the end of the range of movement for jaw clamping and I-beam advance. As shown in a first diagram 4960 of FIG. 109, at both ends 4962, 4966 of the range of movement of a jaw 4968 (acceleration and braking), velocity is limited. A full velocity zone 4964 is provided in the middle of the range of movement. As shown in a second diagram 4970 of FIG. 109, at both ends 4972, 4976 of the range of movement of an I-beam 4978 (acceleration and braking), velocity is limited. A full velocity zone 4974 is provided in the middle of the range of movement.

(563) In addition, control algorithms can be created to provide functional intelligence to the articulation, head rotation, and clamp action. Methods of measuring parameters from the motor 4830 related to the force experienced by the device can also be created that does not measure current or voltage from the motor 4830. FIG. 110 illustrates diagrams 4980, 4982 showing measurement of out-of-phase aspect of the current through the motor 4830. As shown in FIG. 110, the inductor and resistor in parallel to the primary lower H-bridge may be used to determine an out of phase aspect of the current through the motor 4830. The H-bridge 4982 is similar to the motor drive circuit 1165 described in connection with FIG. 50.

(564) In another aspect of the present disclosure, a system comprises a motor 4830 to actuate a mechanism, a motor controller to control the motor velocity or torque, a sensor associated with physical properties of the moving mechanism which is used to adjust a predefined threshold which triggers a change in the motor control operation. In one aspect, motor control speed changes based on the thickness and compressibility of the tissue sensed. In this example, thickness may be measured by linear encoder, and either time to force (velocity) or force reached at a predefined time used to compute the compressibility of the tissue. Tissue stiffness could also be compensated for via measurement of force at two predetermined times or two predetermined positions.

(565) In another aspect, measurement of current and voltage in one or more locations within the kinematic portion of the motor control circuit may be employed to sense dynamic braking and motor acceleration parameters including their impacts by the bodies in rest and in motion that they are influencing. These force/inertia measurements could then be used to change the control parameters of the motor to minimize its effects on the desired motion/force of the actuation body. In addition, a pressure intensity switch can be employed that creates a response in tissue treatment energy proportionate to the intensity of the pressure on the activation button of the device.

(566) In yet another aspect, control methods for adjusting speed, torque, and acceleration of the motor 4830 may be employed. In this aspect, motor control parameters are based on the measured current through the motor 4830. This can be paired with force limiting on clamp arm using either a mechanical force limiting device such as a force limiting spring in line with the motor or through a current limit on the motor to control the force supplied by the motor, thus limiting the clamp arm force. Alternately, use of PWM, pulse amplitude modulation (PAM), pulse position modulation (PPM), or PDM or other signal modification can be used to control motor speed and torque while keeping the motor parameters (voltage, current, etc.) close to the ideal motor voltage/torque balance point.

(567) FIG. 111 is a graph 4990 showing adjustment of velocity limit based on tissue type. A first curve 4992 shown in dashed line represents pre-programmed velocity behavior of a tissue. A second curve 4994 shown in solid line represents actual velocity behavior of a tissue. As shown in graph 4990, it takes a time t_0 for the pre-programmed curve 4992 to reach a threshold velocity v_t , and a pre-programmed velocity limit v_0 is provided for the pre-programmed curve 4992. For the actual velocity curve 4994, it takes at time t_1 which is less than t_0 to reach the threshold velocity v_t . This may indicate that the amount of tissue between the jaws is less than a pre-programmed amount, or that the tissue is thinner than a pre-programmed thickness. The amount of tissue may be detected by two or more sensors located at the jaws and configured to detect tissue presence.

Therefore, a lower revised velocity limit v_1 is provided for the actual velocity curve **4994**. In other aspects of the present disclosure, determination of tissue thickness may be based on any combination of force behavior, gap distance behavior and impedance behavior.

(568) FIG. **112** is a graph **5000** showing different wait periods and different velocity limits in I-beam motor control for tissues with different thickness. A first force curve **5002** and a first velocity curve **5008** (both shown in solid line) represent a thin tissue. A second force curve **5004** and a second velocity curve **5012** (both shown in dash-dot line) represent a medium tissue. A third force curve **5006** and a third velocity curve **5016** (both shown in dash line) represent a thick tissue.

(569) As shown by the first force curve **5002** and the first velocity curve **5008** (thin tissue), in the beginning, the velocity increases to reach a threshold at time t_1 . Thereafter, the velocity is set to be zero, until it starts to increase again at time t_{E1} . The period between time t_1 and time t_{E1} is thin tissue wait period. When the velocity reaches a first velocity limit **5010**, it is kept constant until the force falls to zero, which may indicate the tissue has been cut through.

(570) As shown by the second force curve **5004** and the second velocity curve **5012** (medium tissue), in the beginning, the velocity increases to reach a threshold at time t_2 . Thereafter, the velocity is set to be zero, until it starts to increase again at time t_{E2} . The period between time t_2 and time t_{E2} is medium tissue wait period. When the velocity reaches a second velocity limit **5014**, it is kept constant until the force falls to zero, which may indicate the tissue has been cut through.

(571) As shown by the third force curve **5006** and the third velocity curve **5016** (thick tissue), in the beginning, the velocity increases to reach a threshold at time t_3 . Thereafter, the velocity is set to be zero, until it starts to increase again at time t_{E3} . The period between time t_3 and time t_{E3} is thick tissue wait period. When the velocity reaches a third velocity limit **5018**, it is kept constant until the force falls to zero, which may indicate the tissue has been cut through.

(572) As shown in FIG. **112**, the thicker the tissue is, the longer the wait period is. Also, the thicker the tissue is, the lower the velocity limit is.

(573) FIG. **113** are graphs **5020**, **5030** depicting a relationship between trigger button displacement and sensor output. In both graphs **5020**, **5030**, the vertical axis represents displacement of a trigger button. The trigger button, for example, may be located at a handle assembly or module and is used by a user to control application of RF and/or ultrasonic energy. In both graphs **5020** and **5030**, the horizontal axis represents output of a displacement sensor, for example a Hall sensor. As shown in the first graph **5020**, the sensor output is roughly proportional to the button displacement. A first zone **5022** may be an “OFF” zone, where button displacement is small and no energy is applied. A second zone **5024** may be an “ON” zone or normal energy zone, where button displacement is medium and normal energy is applied. A third zone **5026** may be a “HIGH” zone of increased energy zone, where button displacement is large and energy with high intensity is applied.

Alternatively, the third zone **5026** may be a “HYBRID” zone, where both RF energy and ultrasonic energy are applied. Therefore, more than one active position of the trigger button is provided. In other aspects of the present disclosure, detents instead of continuous travel may be provided for the trigger button. Alternatively, as shown in the second graph **5030**, a three dimensional touch force output level may be provided, where an off zone **5032**, a normal energy zone **5034** and a high energy zone **5036** are provided.

(574) Other aspects of the present disclosure include motor control algorithms used to create tactile feedback (not induced by the normal operation of the mechanism) to indicate to the user the status or limits of a powered actuation. For instance, feedback to surgeon of status of mechanisms or completion of operations is provided. For example, vibration of the device is provided when the energy deliver is finished, or when the impedance curve and force output indicate completion the device is shaken. Or each of the drive systems may have a predefined off center or impact aspect to the very beginning of the strokes allowing the system to repeat moves in opposed directions, and allowing it to create a bigger vibration than the vibration the system can generate within it normal function. In one aspect, there is a specific off-center load mechanism with a dedicated clutch which

allows the device to uncouple from the primary mechanism and couple to this shaker element, allowing it to have a vastly amplified and selectable vibration feedback. There are numerous different shake profiles and intensities which can be used independently or in concert with one another to create differing feedback patterns. The tactile feedback can indicate such things as end of articulation stroke, full clamping is achieved, end of coagulation, error messages such as, but not limited to, the need to reposition the device on tissue or indications that no further energy should be applied to the tissue. For instance the indication of the end of articulation can occur when the user is asking the system to articulate more in a specific direction but the system is at its full limit and is incapable of more articulation in that direction. In this case the motor moves forward and backward fractions of an inch repeatedly shaking the device, thus indicating the device cannot move while not effectively changing the motion of the joint.

(575) Indicating that the user should not apply more energy to the tissue can be done when the device senses that the impedance of the tissue indicates that no more energy should be applied or when the tissue is too thick for energy application or even when an error condition exists such as when RF energy is requested from a modular shaft that only has capabilities for ultrasonic energy activation or when a shaft module is attached to a transducer and the two have mismatched frequencies. Additional examples of this can be found in U.S. Pat. No. 9,364,279, which is herein incorporated by reference in its entirety.

(576) In one aspect, the present disclosure provides a surgical instrument, comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle assembly; a first driver configured to drive movement of at least a first component of the surgical instrument; a second driver configured to drive movement of at least a second component of the surgical instrument; a motor powered by the battery assembly and configured to selectively actuate the first driver or the second driver using an output of the motor; and a controller for the motor, configured to: perform a first limiting operation to the output of the motor when the motor actuates the first driver and a first limiting condition is met, and perform a second limiting operation to the output of the motor when the motor actuates the second driver and a second limiting condition is met.

(577) The end effector may comprise a pair of jaws configured for pivotal movement between a closed position and an open position; and the first driver is configured to drive the pivotal movement. The surgical instrument may further comprise a transducer configured to output an ultrasonic energy, wherein: the second driver is configured to apply a torque to the transducer. The second limiting condition may be met when the torque applied to the transducer reaches a maximum torque.

(578) The shaft may comprise an articulation joint, a first portion of the shaft comprising the proximal end, and a second portion of the shaft comprising the distal end, the first and second portions being coupled about the articulation joint; the second portion of the shaft is configured for articulation movement about the articulation joint; and the first driver is configured to drive the articulation movement.

(579) The second driver may be configured to drive axial rotation the second portion. The surgical instrument may further comprise a blade, wherein: the first or second driver is configured to advance the blade. The surgical instrument may further comprise a third driver configured to drive movement of at least a third component of the surgical instrument, wherein: the motor is configured to selectively actuate the first driver, the second driver or the third driver using the output; and the controller for the motor is further configured to perform a third limiting operation to the output of the motor when the motor actuates the third driver and a third limiting condition is met.

(580) The first limiting condition may be met when the output of the motor reaches a first maximum velocity; and the second limiting condition may be met when the output of the motor

reaches a second maximum velocity. The first limiting condition may be met when a current of the motor reaches a first maximum current; and the second limiting condition may be met when the current of the motor reaches a second maximum current. The first limiting operation may control the current of the motor to be substantially zero. The second limiting operation may control the current of the motor to be substantially equal to the second maximum current.

(581) The first limiting condition may define a first maximum velocity profile of the output of the motor over a range of the movement of the first component; and the second limiting condition defines a second maximum velocity profile of the output of the motor over a range of the movement of the second component.

(582) The first maximum velocity profile may comprise a first limited velocity region near one end of the range of the movement of the first component, a second limited velocity region near the other end of the range of the movement of the first component, and a first full velocity region between the first and second limited velocity regions; and the second maximum velocity profile comprises a third limited velocity region near one end of the range of the movement of the second component, a fourth limited velocity region near the other end of the range of the movement of the second component, and a second full velocity region between the third and fourth limited velocity regions.

(583) In another aspect, the present disclosure provides, a method for operating a surgical instrument, the surgical instrument comprising a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft, and a handle assembly coupled to a proximal end of the shaft, the method comprising: selectively actuating a first driver or a second driver using an output of a battery-powered motor; driving, with the first driver, movement of at least a first component of the surgical instrument when the motor actuates the first driver; performing a first limiting operation to the output of the motor when the motor actuates the first driver and a first limiting condition is met; driving, with the second driver, movement of at least a second component of the surgical instrument when the motor actuates second driver; and performing a second limiting operation to the output of the motor when the motor actuates the second driver and a second limiting condition is met.

(584) The driving movement of at least a first component of the surgical instrument may comprise driving a pivotal movement of a pair of jaws of the end effector between a closed position and an open position. The driving movement of at least a second component of the surgical instrument may comprise applying a torque to a transducer configured to output an ultrasonic energy. The first limiting condition is met when a current of the motor may reach a first maximum current; and the second limiting condition may be met when the current of the motor reaches a second maximum current.

(585) In another aspect, the present disclosure provides a surgical instrument, comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft; a handle assembly coupled to a proximal end of the shaft, the handle assembly comprising a button configured to be displaced when pressed by a user; a battery assembly coupled to the handle assembly; a driver configured to drive movement of at least one component of the surgical instrument; a motor powered by the battery assembly and configured to actuate the driver using an output of the motor; and a controller for translating displacement of the button to a velocity of the motor, the controller being configured to: detect a movement of the button having frequency above a frequency threshold and magnitude below a magnitude threshold; and perform a smoothing operation on the movement when translating the displacement to the velocity of the motor. The end effector may comprise a pair of jaws configured for pivotal movement between a closed position and an open position; and the driver is configured to drive the pivotal movement.

(586) In another aspect, the present disclosure provides a surgical instrument, comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle

assembly; a driver configured to drive movement of at least one component of the surgical instrument; a motor powered by the battery assembly and configured to actuate the driver using an output of the motor; and a controller for the motor, configured to perform a first limiting operation to the output of the motor when a first limiting condition is met, wherein the first limiting condition defines a maximum control variable profile of the motor over a range of the movement of the at least one component.

(587) The maximum control variable profile may be a non-constant control variable profile. The maximum control variable profile may be a non-linear control variable profile. The first limiting operation may comprise decreasing a velocity of the motor.

(588) The controller may be further configured to perform a second limiting operation to the output of the motor when a second limiting condition is met, wherein the second limiting condition defines a minimum control variable profile of the motor over the range of the movement of the at least one component. The second limiting operation may comprise increasing a velocity of the motor.

(589) The controller may be further configured to: apply a first velocity profile of the motor that decreases over time when a rate of increase of the current of the motor is above a first threshold, and apply a second velocity profile of the motor that increases over time when a rate of decrease of the current of the motor is above a second threshold.

(590) The end effector may comprise a pair of jaws configured for pivotal movement between a closed position and an open position; and the driver is configured to drive the pivotal movement. The surgical instrument may further comprise a transducer configured to output an ultrasonic energy, wherein: the driver is configured to apply a torque to the transducer. The surgical instrument may further comprise a blade, wherein: the driver is configured to advance the blade. The control variable profile of the motor may be any one of a current profile of the motor or a voltage profile of the motor.

(591) In another aspect the present disclosure provides, a surgical instrument, comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle assembly; a driver configured to drive movement of at least one component of the surgical instrument; a motor powered by the battery assembly and configured to actuate the driver using an output of the motor; and a controller for the motor, configured to perform a limiting operation to the output of the motor when a limiting condition is met, wherein the limiting condition defines a maximum velocity profile of the motor over a range of the movement of the at least one component.

(592) The maximum velocity profile may be a non-constant velocity profile. The maximum velocity profile may be a non-linear velocity profile. The maximum velocity profile may comprise a first limited velocity zone near one end of a range of movement of the at least one component, a second limited velocity zone near the other end of the range of movement of the at least one component, and a full velocity zone between the first and second limited velocity zones.

(593) The end effector may comprise a pair of jaws configured for pivotal movement between a closed position and an open position; and the driver is configured to drive the pivotal movement. The surgical instrument may further comprise a transducer configured to output an ultrasonic energy, wherein: the driver is configured to apply a torque to the transducer. The surgical instrument may further comprise a blade, wherein: the driver is configured to advance the blade.

(594) In another aspect, the present disclosure provides a method for operating a surgical instrument, the surgical instrument comprising a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft, and a handle assembly coupled to a proximal end of the shaft, the method comprising: actuating a driver using an output of a battery-powered motor; driving, with the driver, movement of at least one component of the surgical instrument; and performing a first limiting operation to the output of the motor when a first limiting condition is

met, wherein the first limiting condition defines a maximum control variable profile of the motor over a range of the movement of the at least one component. The first limiting operation may comprise decreasing a velocity of the motor. The method may further comprise performing a second limiting operation to the output of the motor when a second limiting condition is met, wherein the second limiting condition defines a minimum control variable profile of the motor over the range of the movement of the at least one component. The control variable profile of the motor may be any one of a current profile of the motor or a voltage profile of the motor.

(595) In one aspect, the present disclosure provides a surgical instrument, comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle assembly; a driver configured to drive movement of at least one component of the surgical instrument; a motor powered by the battery assembly and configured to actuate the driver using an output of the motor; and a controller for the motor, configured to perform a limiting operation to the output of the motor when a limiting condition is met, wherein the limiting condition is determined based at least in part on a tissue characteristic.

(596) The end effector may comprise at least two sensors configured to detect tissue presence, and the tissue characteristic is an amount of tissue detected by the at least two sensors. The tissue characteristic may be tissue thickness. The limiting condition may be a maximum velocity of the motor determined based at least in part on the tissue thickness.

(597) The controller may be further configured to apply a delay between when the driver is first actuated and when the driver is actuated again, wherein a length of the delay is determined based at least in part on the tissue characteristic. The end effector may comprise a pair of jaws configured for pivotal movement between a closed position and an open position; and the driver is configured to drive the pivotal movement.

(598) The surgical instrument may further comprise a transducer configured to output an ultrasonic energy, wherein: the driver is configured to apply a torque to the transducer. The surgical instrument may further comprise a blade, wherein: the driver is configured to advance the blade.

(599) In another aspect, the present disclosure provides a method for operating a surgical instrument, the surgical instrument comprising a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft, and a handle assembly coupled to a proximal end of the shaft, the method comprising: actuating a driver using an output of a battery-powered motor; driving, with the driver, movement of at least one component of the surgical instrument; determining, based at least in part on a tissue characteristic, a limiting condition; and performing a limiting operation to the output of the motor when the limiting condition is met.

(600) The tissue characteristic may be tissue thickness. The limiting condition may be a maximum velocity of the motor determined based at least in part on the tissue thickness. The method may further comprise applying a delay between when the driver is first actuated and when the driver is actuated again, wherein a length of the delay is determined based at least in part on the tissue characteristic. The driving movement of at least one component of the surgical instrument may comprise advancing a blade of the surgical instrument.

(601) In another aspect, the present disclosure provides, a surgical instrument, comprising: a shaft assembly comprising a shaft and an end effector coupled to a distal end of the shaft; a handle assembly coupled to a proximal end of the shaft; a battery assembly coupled to the handle assembly; a driver configured to drive movement of at least one component of the surgical instrument; a motor powered by the battery assembly and configured to actuate the driver using an output of the motor; and a controller for the motor, configured to provide a tactile feedback to a user with the at least one component.

(602) The at least one component may be dedicated for providing the tactile feedback. The at least one component may be configured to handle or treat a tissue.

(603) The controller may be configured to provide the tactile feedback when a desired operation of

the surgical instrument is competed. The controller may be configured to provide the tactile feedback when an error has occurred. The controller may be configured to provide the tactile feedback when the surgical instrument cannot provide a desired type of energy. The controller may be configured to provide the tactile feedback when a transducer configured to output ultrasonic energy is coupled to a transducer driver having a mismatched frequency.

Modular Battery Powered Handheld Surgical Instrument with Multi-Function Motor Via Shifting Gear Assembly

(604) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with multi-function motor via shifting gear assembly. Disclosed is a modular handheld surgical instrument that includes a modular handle assembly, a modular ultrasonic transducer assembly and a modular shaft assembly is disclosed. The modular handle assembly includes a shift gear translatable between a first position and a second position, wherein when the shift gear is translated to the first position, the surgical instrument is configured to rotate a drive gear of a first shaft of the modular shaft assembly to perform at least one shaft actuation function and when the shift gear is translated to the second position, the surgical instrument is configured to rotate a torque gear of a second shaft of the modular shaft assembly to controllably torque an ultrasonic waveguide of the modular shaft assembly to an ultrasonic transducer of the modular ultrasonic transducer assembly to a predefined torque.

(605) Before discussing aspects of the present disclosure in detail, a modular handheld surgical instrument is generally disclosed as using a single motor to drive not only multiple independent shaft functions (e.g., shaft rotation, jaw closure, etc.) but also torque limited attachment of an ultrasonic waveguide to an ultrasonic transducer, wherein electronic clutching/shifting may be used to switch between functions. The modular handheld surgical instrument may provide torque limited motor driven attachment of the ultrasonic waveguide via the same motor in the handle that controls shaft actuation of clamping, rotation and/or articulation. A shifting assembly in the handle may move a gear from a primary drive assembly to a spur gear to allow the motor to rotate the nozzle/shaft/waveguide. The shifting assembly may also activate the motor inducing the handle to torque the waveguide into place with a pre-desired minimum torque. For instance, the handle housing may have a transducer torqueing mechanism which shifts the motor longitudinally uncoupling the primary drive shaft spur gear and coupling the transducer torqueing gear which rotates the shaft and nozzle therefore screwing the ultrasonic waveguide into/onto the ultrasonic transducer.

(606) Turning now to FIGS. **114-116** there is shown a sequence of events for attaching and torqueing an ultrasonic waveguide in a battery powered modular handheld surgical instrument according to an aspect of the present disclosure. With reference to FIGS. **114-116**, a system **3000** includes a modular handle assembly housing **3002** comprising a motor assembly **3620** (e.g., FIG. **125**) and a shifting assembly **3022**. The motor assembly **3620** comprises a motor **3004** and a shaft **3006** to rotate a primary gear **3008** (e.g., motor gear). The shaft **3006** of the motor **3004** extends through a first aperture defined in a distal portion of the modular handle assembly housing **3002**. The shifting assembly **3022** comprises a shifting bar **3024**, a shaft **3026**, a spring **3028**, and a shifting spur gear **3012**. The shaft **3026** of the shifting assembly **3022** extends through a second aperture defined in the distal portion of the modular handle assembly housing **3002** such that the shaft **3026** of the shifting assembly **3022** is positioned substantially parallel to the shaft **3006** of the motor **3004**. Teeth **3010** of the primary gear **3008** are meshingly engageable with teeth **3014** of the shifting spur gear **3012** to realize multiple functions of the system **3000**. System functions include shaft actuation functions such as clamping, rotation, and articulation, via a primary drive gear **3016**, and coupling functions, wherein an ultrasonic waveguide **3032** of a modular shaft assembly **3030** being attached to a modular handle assembly **3060** is coupleable, via a slip clutch gear **3020** (e.g., torque gear), to an ultrasonic transducer shaft **3044** of a modular ultrasonic transducer assembly **3040**. In one particular aspect of the present disclosure, throughout the coupling function, torque

applied by the motor **3004** is limited.

(607) FIG. **114** shows a stage in the sequence of events for attaching and torquing an ultrasonic waveguide in the system **3000**. FIG. **114** is an elevation view of the system **3000** wherein the modular ultrasonic transducer assembly **3040** is attached to the modular handle assembly **3060**. FIG. **114** shows a modular ultrasonic transducer assembly housing **3042** installed against the modular handle assembly housing **3002**. In one example aspect of the present disclosure, the modular ultrasonic transducer assembly **3040** comprises a transducer subassembly **3050** including an ultrasonic transducer **3054** that defines a cylindrical distal portion, having teeth **3046** arranged radially about its external surface, and a ultrasonic transducer shaft **3044** that extends distally through an aperture defined in a distal portion of the modular ultrasonic transducer assembly housing **3042**. The distal end of the ultrasonic transducer shaft **3044** includes an externally threaded portion **3048**. The threaded portion **3048** extends proximally from the distal end toward the transducer **3054** a specified length. Further in view of FIG. **114**, a modular shaft assembly **3030**, comprising a cylindrical ultrasonic waveguide **3032**, is shown positioned for attachment to the modular handle assembly **3060** and the modular ultrasonic transducer assembly **3040**.

(608) As shown in FIG. **114**, the ultrasonic waveguide **3032** extends proximally from the modular shaft assembly **3030** a specified length. In the example aspect of the present disclosure, the proximal end of the ultrasonic waveguide **3032** comprises a chamfer **3034** as well as internal threads **3106** (See FIG. **115**) configured to receive the threaded portion **3048** of the ultrasonic transducer shaft **3044**. Notably, as shown in the example aspect of FIG. **114**, when the modular shaft assembly **3030** is positioned for attachment to the modular handle assembly **3060** and the modular ultrasonic transducer assembly **3040**, a sloped face **3036** of the chamfer **3034** is positioned in interfering alignment with the distal end of the threaded portion **3048**. In one example aspect, the distal tip of the threaded portion **3048** may be configured to interact with the sloped face **3036** of the chamfer **3034** (e.g., threaded portion **3048** may also comprise a chamfer). In an alternative aspect of the present disclosure, the ultrasonic transducer shaft **3044** could comprise the chamfer and the internal threads while the ultrasonic waveguide **3032** comprises the external threaded portion and the optional chamfer.

(609) FIG. **115** shows another stage in the sequence of events for attaching and torquing an ultrasonic waveguide in the system **3000**. FIG. **115** is another elevation view of system **3000** shown in FIG. **114** wherein the transducer subassembly **3050** of the modular ultrasonic transducer assembly **3040** further comprises a spring **3102** positioned in a compressive state between a proximal end of transducer subassembly **3050** and a proximal portion of the modular ultrasonic transducer assembly housing **3042**. As shown in FIG. **114** the spring **3102** is configured to force the transducer subassembly **3050** distally within the modular ultrasonic transducer assembly housing **3042** such that the ultrasonic transducer shaft **3044** extends through the aperture defined in the distal portion of the modular ultrasonic transducer assembly housing **3042**.

(610) Turning again to FIGS. **114-115**, as the modular shaft assembly **3030** is being attached to the modular handle assembly **3060** and the modular ultrasonic transducer assembly **3040**, prior to a coupling between the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044**, the chamfer **3034** at the proximal end of the ultrasonic waveguide **3032** interferingly interfaces with the distal end of the threaded portion **3048** of the ultrasonic transducer shaft **3044**. In the example aspect, the sloped face **3036** of the chamfer **3034** interacts with the distal end of the threaded portion **3048** causing the transducer subassembly **3050** to translate proximally against (e.g., further compressing) the spring **3102**. When the modular shaft assembly **3030** is fully seated against and/or attached to the modular handle assembly **3060**, the ultrasonic waveguide **3032** is axially aligned with the ultrasonic transducer shaft **3044** and the spring **3102** naturally forces the transducer subassembly **3050** distally such that the distal end of the threaded portion **3048** of the ultrasonic transducer shaft **3044** interfaces with the internal threads **3106** at the proximal end of the ultrasonic waveguide **3032**. Such an interface provides multiple advantages.

(611) For example, after the chamfer **3034** interacts with the threaded portion **3048**, tactile feedback (e.g., click and/or vibration) may be produced when the spring **3102** forces the threaded portion **3048** of the ultrasonic transducer shaft **3044** against the internal threads **3106** of the ultrasonic waveguide **3032**. This indicates to the user not only that the modular shaft assembly **3030** is fully seated against the modular handle assembly **3060** but also that the ultrasonic transducer shaft **3044** is axially aligned with the ultrasonic waveguide **3032** and that a coupling between the ultrasonic transducer shaft **3044** and the ultrasonic waveguide **3032** can commence. As another example, when the spring **3102** forces the threaded portion **3048** against the internal threads **3106** the applied pressure enables the threaded portion **3048** to screw into the internal threads **3106**. This is ideal since the threaded portion **3048** and the internal threads **3106** are concealed from view when the modular ultrasonic transducer assembly **3040** and the modular shaft assembly **3030** are attached to the modular handle assembly **3060**.

(612) Referring to FIGS. **114-116**, the shifting assembly **3022** is translatable distally (e.g., FIG. **116**) and proximally (e.g., FIG. **115**) while the shifting spur gear **3012** is engaged with primary gear **3008**. For example, the shifting spur gear **3012** is translatable between at least a first position (e.g., FIG. **115**, **3104**) and a second position (e.g., FIG. **116**, **3202**). Furthermore, the primary gear **3008** comprises teeth **3010** of a longitudinal width to accommodate translation of the shifting spur gear **3012** between at least the first position **3104** and the second position **3202**. In an alternative aspect, the primary gear **3008** comprises teeth **3010** of a longitudinal width to accommodate translation of the shifting spur gear **3012** to a position where the teeth **3014** of the shifting spur gear **3012** are not meshingly engaged with the teeth **3018** of the primary drive gear **3016** or the teeth **3022** of the slip clutch gear **3020** (e.g., a neutral position). In yet another alternative aspect, it should be appreciated that, in lieu of the shifting assembly **3022**, the motor assembly **3620** may be configured to shift/translate (e.g., in a manner similar to the shifting assembly **3022**) distally and proximally within the modular handle assembly housing **3002** such that the primary gear **3008** engages the primary drive gear **3016** in the first position **3104** and engages the slip clutch gear **3020** in the second position **3202**.

(613) Looking to FIG. **115**, in the first position **3104**, the teeth **3014** of the shifting spur gear **3012** meshingly engage the teeth **3018** of the primary drive gear **3016**. In the example aspect, the primary drive gear **3016**, when rotated by the motor **3004** via the primary gear **3008** and the shifting spur gear **3012**, is configured to perform shaft actuation functions such as clamping, rotation, and/or articulation. In other aspects, the primary drive gear **3016** may be configured to perform other desired shaft and/or end effector functions upon rotation. In one aspect, in view of FIG. **117**, the primary drive gear **3016** may rotate a primary rotary drive **3304** (FIG. **118**) including a first internal shaft **3306**, a cylindrical coupler **3308**, and a second internal shaft **3310**. The primary drive gear **3016** is fixedly attached to a proximal end of the first internal shaft **3306**. In such an aspect, the cylindrical coupler **3308** may be utilized to convert the rotational motion from the primary drive gear **3016** to translational motion (e.g., to realize the desired shaft/end effector actuation functions). Here, a proximal end of the cylindrical coupler **3308** may be fixedly attached to a distal end of the first internal shaft **3306**. A distal end of the cylindrical coupler **3308** may comprise internal threads **3320** to meshingly engage external threads **3322** on a proximal end of the second internal shaft **3310** to cause the second internal shaft **3310** to translate distally and/or proximally a defined distance (e.g., 2 mm) to perform one or more independent shaft actuation functions (e.g., jaw closure, articulation, etc.).

(614) In one example aspect, in view of FIG. **117**, the second internal shaft **3310** may include a magnet **3324**. In such an aspect, a sensor **3326** (e.g., hall sensor) may be positioned externally to detect/monitor the distal and/or proximal translation of the second internal shaft **3310**. It should be appreciated that the second internal shaft **3310** of the primary rotary drive **3304** is restrictable from rotation distal of the threaded interface between the cylindrical coupler **3308** and the second internal shaft **3310** such that the second internal shaft **3310** is translatable distally and/or

proximally. In one aspect, in view of FIG. 119, an exterior shaft 3038 may be fixedly coupled to the ultrasonic waveguide 3032 via pins 3344, 3346 that extend from the exterior shaft 3038 through longitudinal cutouts 3340, 3342 (e.g., defined in the second internal shaft 3310) to the ultrasonic waveguide 3032.

(615) Here, in light of FIGS. 115, 119, when the shifting spur gear 3012 is in the first position 3104 (e.g., when performing shaft actuation functions), the exterior shaft 3038 is selectively coupleable to a fixed external housing 3330 (e.g., housing of the modular shaft assembly 3030) via an actuatable exterior shaft lock mechanism 3356, 3358 (e.g., push button, lock pin, etc.). In such an aspect, the exterior shaft 3038 may comprise a detent 3352, 3354 to accommodate the exterior shaft lock mechanism 3356, 3358. For example, the detent 3352, 3354 may be configured to receive a tip of the exterior shaft lock mechanism 3356, 3358 to selectively restrict the exterior shaft 3038 from rotating.

(616) FIG. 119 shows the exterior shaft lock mechanism 3356 in an actuated state. When the exterior shaft 3038 is restricted from rotation by the exterior shaft lock mechanism 3356, 3358 and detent 3352, 3354, the second internal shaft 3310 is also restricted from rotation via the pins 3344, 3346. Notably, in such an aspect, although the second internal shaft 3310 is restricted from rotation, the second internal shaft 3310 remains translatable distally and/or proximally (e.g., pins 3344, 3346 permit distal and/or proximal translation via the longitudinal cutouts 3340, 3342) to perform the desired shaft actuation functions. In various aspects, the longitudinal cutouts 3340, 3342 and the pins 3344, 3346 may be positioned at or about an antinode of the ultrasonic waveguide 3032.

(617) Furthermore, it should be appreciated that distal versus proximal translation of the second internal shaft 3310 is a function of the motor 3004 rotation direction (e.g., clockwise versus counter-clockwise) and thread direction (e.g., right-handed threads versus left-handed threads) at the threaded interface between the cylindrical coupler 3308 and the second internal shaft 3310. Further, in an alternative aspect, it should be appreciated that if rotational motion is desired to perform shaft actuation functions, the primary rotary drive 3304 may simply comprise the first internal shaft 3306. In such an aspect, the motor 3004 would rotate the primary drive gear 3016 to rotate the first internal shaft 3306 to perform desired shaft actuation functions using clockwise and counter-clockwise rotation directions. In various aspects, the primary rotary drive 3304 (e.g., the first internal shaft 3306, the cylindrical coupler 3308, second internal shaft 3310) is supported between the ultrasonic waveguide 3032 and/or the exterior shaft 3038 (e.g., via bearings, lubricious seals/o-rings/spacers, combinations thereof, etc.).

(618) FIG. 116 shows another stage in the sequence of events for attaching and torquing an ultrasonic waveguide in the system 100. Turning to FIG. 116, in the second position 3202, the teeth 3014 of the shifting spur gear 3012 meshingly engage the teeth 3022 of the slip clutch gear 3020. Notably, in light of FIG. 119, when the shifting spur gear 3012 is in the second position 3202, the exterior shaft 3038 is selectively uncoupleable from the fixed external housing 3330 (e.g., housing of the modular shaft assembly 3030) via the exterior shaft lock mechanism 3356, 3358. FIG. 119 shows the exterior shaft lock mechanism 3358 in an unactuated state. In such an aspect, when the exterior shaft lock mechanism 3356, 3358 is unactuated, the tip of the exterior shaft lock mechanism is withdrawn from the detent 3352, 3354 in the exterior shaft 3038 to permit the exterior shaft 3038 to rotate.

(619) As such, in the example aspect, the slip clutch gear 3020 when rotated by the motor 3004 via the primary gear 3008 and the shifting spur gear 3012, is configured to rotate the exterior shaft 3038 and the ultrasonic waveguide 3032 coupled thereto (FIG. 119, e.g., the exterior shaft 3038 may be coupled to the ultrasonic waveguide 3032 via the pins 3344, 3346 that extend from the exterior shaft 3038 to the ultrasonic waveguide 3032). In such an aspect, rotation of the exterior shaft 3038 also rotates the ultrasonic waveguide 3032 causing the internal threads 3106 (FIG. 115) of the ultrasonic waveguide 3032 to screw onto the threaded portion 3048 of the ultrasonic transducer shaft 3044. In light of FIGS. 115-116, the transducer subassembly 3050 translates

distally as the ultrasonic waveguide **3032** screws onto the ultrasonic transducer shaft **3044**. In such an aspect, although the second internal shaft **3310** will also rotate (e.g., via pins **3344**, **3346**), the primary drive gear **3016** is free to rotate since the shifting spur gear **3012** is at the second position **3202**.

(620) In various aspects, the ultrasonic transducer shaft **3044**, at a proximal end of threaded portion **3048** may comprise a receiving face **3056** (FIG. **114**) configured and/or shaped to receive the sloped face **3036** of the chamfer **3034**. When the ultrasonic waveguide **3032** is fully screwed onto the threaded portion **3048**, the receiving face **3056** makes surface contact with the sloped face **3036** of the chamfer **3034** (FIG. **116**). As further described below, the motor **3004** may be torque limited when the ultrasonic waveguide **3032** is screwed onto the threaded portion **3048** to control the torque experienced at the interface between receiving face **3056** and sloped face **3036**.

(621) In one alternative aspect of the present disclosure, in lieu of screwing the ultrasonic waveguide **3032** onto/into the ultrasonic transducer shaft **3044** as described herein, the ultrasonic transducer shaft **3044** may be screwed onto/into the ultrasonic waveguide **3032**. In view of FIGS. **10A-10B**, a shifting worm gear **206** may rotatably interface with teeth **202** of the ultrasonic transducer **130** to advance/screw/couple a threaded portion of the ultrasonic transducer shaft **156** into the ultrasonic waveguide **145**. It should be appreciated that the shifting worm gear **206** may also rotatably interface with the teeth **202** of the ultrasonic transducer **130** to withdraw/unscrew/uncouple the threaded portion of the ultrasonic transducer shaft **156** from the ultrasonic waveguide **145**.

(622) FIGS. **120-121** depict a torque lever for use in a device according to an aspect of the present disclosure. As previously discussed, the shifting assembly **3022**, comprising the shifting bar **3024**, the shaft **3026**, the spring **3028**, and the shifting spur gear **3012**, is translatable distally and proximally within the modular handle assembly **3060**. In FIG. **120**, a top elevation view of the system **3000**, the shifting assembly **3022** further includes a torque lever **3402** and a shift linkage **3414**. The torque lever **3402** includes a first flange **3406** and a second flange **3408** and is pivotable about a lever pivot **3404**. The first flange **3406** protrudes in a direction transverse to the lever pivot **3404** and may extend at least partially outside the modular handle assembly housing **3002**. Notably, in the example aspect, the first flange **3406** is located for manual actuation by a user between a first point **3410** and a second point **3412**. In an alternative aspect, an automated mechanism (e.g., servo motor, user accessible actuation button, etc.) may be configured to actuate the first flange **3406** between the first point **3410** and the second point **3412** (e.g., inside the modular handle assembly housing **3002**). Furthermore, the first flange **3406** may comprise ribs **3434** for a user to grip and pivot the torque lever **3402** (FIG. **121**). The second flange **3408** protrudes in a direction transverse to the lever pivot **3404** and is coupled to the shifting bar **3024** and the shift linkage **3414** at a first shift pin **3416**.

(623) In light of FIGS. **115**, **116**, **120**, and **122**, the shifting bar **3024**, in response to movement of the first flange **3406** of the torque lever **3402** between the first point **3410** toward the second point **3412**, is operable to compress the spring **3028**, positioned about the shaft **3026** between a portion of the shifting bar **3024** and a distal portion of the modular handle assembly housing **3002**, to translate the shifting spur gear **3012** (e.g., while engaged with the primary gear **3008**) from a first position **3104** (e.g., where the shifting spur gear **3012** is engaged with the primary drive gear **3016**) to a second position **3202** (e.g., where the shifting spur gear **3012** is engaged with the slip clutch gear **3020**). Notably, in light of FIG. **122**, the shifting assembly **3022** may be configured to naturally lock (e.g., to resist the force of the spring **3028**) when the first flange **3406** of the torque lever **3402** has been pivoted to the second point **3412**. In an alternative aspect, the shifting assembly **3022** may utilize a separate lock (not shown) to maintain the shifting spur gear **3012** in the second position **3202**. In one aspect, an alternative mechanism to force the shifting assembly **3022** proximally (e.g., spring coupled/attached to shifting assembly **3022** in an alternative manner) may be utilized. In light of FIGS. **120** and **122**, it should be appreciated that, in response to

movement of first flange **3406** of the torque lever **3402** between the second point **3412** toward the first point **3410**, the shifting bar **3024** is operable to release compression of the spring **3028** to translate the shifting spur gear **3012** from the second position **3202** to the first position **3104**. (624) Furthermore, in the example aspect of FIG. **122**, a distal end of the shaft **3026** may be configured to contact/actuate a first shift switch **3504** during distal translation of the shifting assembly **3022**. The first shift switch **3504** may be normally in an unactuated “off” position. When the first flange **3406** of the torque lever **3402** is fully pivoted to the second point **3412**, the distal end of shaft **3026** may interferingly actuate the first shift switch **3504** to an “on” position (e.g., FIG. **116**). In the example aspect, the first shift switch **3504** comprises leads electrically coupled to the motor control circuit **726** (FIG. **36**) and/or the motor drive circuit **1165** (FIG. **50**). The motor control circuit **726** and/or the motor drive circuit **1165** may be configured to automatically turn the motor **3004** “on” when the first shift switch **3504** is actuated. Notably, when the first flange **3406** of the torque lever **3402** is pivoted to the second point **3412**, the shifting spur gear **3012** is engaged with the slip clutch gear **3020** (e.g., FIG. **116**). As such, when the first shift switch **3504** is actuated, the motor **3004** may be configured to automatically couple or begin coupling the ultrasonic waveguide **3032** to the ultrasonic transducer shaft **3044**. In one alternative aspect, when the first shift switch **3504** is actuated, a separate control on the modular handle assembly **3060** may be actuatable to couple or begin coupling the ultrasonic waveguide **3032** to the ultrasonic transducer shaft **3044**. In such an aspect, the motor control circuit **726** and/or the motor drive circuit **1165** is configured to turn the motor **3004** “on” when the separate control on the modular handle assembly **3060** is actuated.

(625) In an alternative aspect, the motor control circuit **726** (FIG. **36**) and/or the motor drive circuit **1165** (FIG. **50**) may be configured to disable operation of the motor **3004** until the first shift switch **3504** or a second shift switch (not shown) is actuated. In such an aspect, the second shift switch may be positioned for actuation when the first flange **3406** of the torque lever **3402** is fully pivoted to the first point **3410** (e.g., when the shifting spur gear **3012** is engaged with the primary drive gear **3016**). The second shift switch may comprise leads electrically coupled to the motor control circuit **726** and/or the motor drive circuit **1165**. In such an aspect, the motor control circuit **726** and/or the motor drive circuit **1165** may be operable, via the first shift switch **3504** and the second shift switch, to disable the motor **3004** until one of the first shift switch **3504** or the second shift switch is actuated. A separate control on the modular handle assembly **3060** may be actuatable to selectively operate the motor **3004** when one of the first shift switch **3504** or the second shift switch is actuated. This advantageously prevents unintentional actuation of the motor **3004** as well as any potential for grinding between the shifting spur gear **3012** and the primary drive gear **3016** and/or the slip clutch gear **3020** as the shifting spur gear **3012** translates from the first position **3104** to the second position **3202**.

(626) Further in view of FIGS. **77** and **79**, the shift linkage **3414**, in response to movement of the first flange **3406** of the torque lever **3402** between the first point **3410** and the second point **3412**, is configured to operate a transducer locking mechanism **3418** via a second shift pin **3420**. The transducer locking mechanism **3418** includes a lock bar **3422** and a pin **3424**. The pin **3424** is configured to travel within a slot **3426**, which may be defined in the modular handle assembly housing **3002**, between an unlocked position **3428** (e.g., FIG. **120**) and a locked position **3502** (e.g., FIG. **122**). In the example aspect, when the first flange **3406** of the torque lever **3402** is pivoted to the first point **3410**, the pin **3424** is in the unlocked position **3428** and when the first flange **3406** of the torque lever **3402** is pivoted to the second point **3412**, the pin **3424** is in the locked position **3502**.

(627) Further in view of FIG. **120**, a first end of the lock bar **3422** includes the pin **3424** and a keyed surface **3430**. The keyed surface **3430** is configured to lock the ultrasonic transducer **3054**. A second end of the lock bar **3422** is coupled to the shift linkage **3414** at the second shift pin **3420** so that rotation of the torque lever **3402** about the lever pivot **3404** operates the transducer locking

mechanism **3418**. In one various aspect, the shift linkage **3414** is shaped to accommodate the torque lever **3402** as it pivots about the lever pivot **3404**. For example, in view of FIG. **120**, the shift linkage **3414** comprises an arcuate shape to accommodate a round body of the torque lever **3402** to conserve space within the modular handle assembly housing **3002**.

(628) Further in view of FIG. **120**, when the pin **3424** of the transducer locking mechanism **3418** is in the unlocked position **3428**, the keyed surface **3430** of the lock bar **3422** is disengaged from the ultrasonic transducer **3054**. In view of FIG. **122**, as the first flange **3406** of the torque lever **3402** is pivoted from the first point **3410** to the second point **3412**, the pin **3424** travels within the slot **3426** from the unlocked position **3428** toward the locked position **3502**. When the pin **3424** is in the locked position **3502**, the keyed surface **3430** engages the ultrasonic transducer **3054** to control movement of the ultrasonic transducer **3054** (e.g., via teeth **3046**) and the ultrasonic transducer shaft **3044**. In one aspect, the keyed surface **3430** may be configured to restrict rotation while permitting proximal and distal translation of the transducer subassembly **3050**. In such an aspect, the teeth **3046** of the ultrasonic transducer **3054** comprise a longitudinal width to accommodate translation of the transducer subassembly **3050** (FIGS. **114-116**, e.g., as the ultrasonic waveguide **3032** is screwed onto/into the ultrasonic transducer shaft **3044**). In one example aspect, the keyed surface **3430** comprises teeth **3432** (FIG. **121**) configured to meshingly engage the teeth **3046** of the ultrasonic transducer **3054**. Notably, locking the ultrasonic transducer **3054** from rotation, via the transducer locking mechanism **3418**, permits the system **3000** to limit torque applied by the motor **3004** when coupling the ultrasonic waveguide **3032** and ultrasonic transducer shaft **3044**.

(629) The above aspects describe numerous structures to couple the ultrasonic waveguide **3032** of a modular shaft assembly **3030** and the ultrasonic transducer shaft **3044** of a modular ultrasonic transducer assembly **3040**. The above aspects also describe numerous structures not only to torque the ultrasonic waveguide **3032** to the ultrasonic transducer shaft **3044** but also to limit that torque in a controlled manner. In particular, when a modular ultrasonic transducer assembly **3040** and a modular shaft assembly **3030** are attached to a modular handle assembly **3060** such that the ultrasonic waveguide **3032** of the modular shaft assembly **3030** is axially aligned with the ultrasonic transducer shaft **3044** of the modular ultrasonic transducer assembly (e.g., described above, FIG. **114**), the first flange **3406** of the torque lever **3402** may be pivoted from the first point **3410** toward the second point **3412** (e.g., described above, FIGS. **120, 129**). As the first flange **3406** of the torque lever **3402** approaches the second point **3412** movement of the ultrasonic transducer **3054** and the ultrasonic transducer shaft **3044** is controlled via the transducer locking mechanism **3418** (e.g., rotation restricted while translation permitted).

(630) Simultaneously, while the first flange **3406** of the torque lever **3402** is pivoted from the first point **3410** toward the second point **3412**, the shaft **3026** and the shifting spur gear **3012** are translated distally so that the shifting spur gear **3012** can engage slip clutch gear **3020** and the distal end of the shaft **3026** can actuate the first shift switch **3504**. When the first flange **3406** of torque lever **3402** reaches the second point **3412**, the shifting spur gear **3012** engages the slip clutch gear **3020** and the distal end of the shaft **3026** actuates the first shift switch **3504**. Upon actuation of the first shift switch **3504**, the motor **3004** may rotate the slip clutch gear **3020** via the shifting spur gear **3012** to rotate the exterior shaft **3038** coupled to the ultrasonic waveguide **3032**. Since the ultrasonic transducer **3054** is in a locked state (e.g., rotation prevented), rotation of the exterior shaft **3038** rotates the ultrasonic waveguide **3032** relative to the ultrasonic transducer shaft **3044** such that ultrasonic waveguide **3032** screws onto the ultrasonic transducer shaft **3044** thereby coupling the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044**. Such a coupling occurs internal to the device since the modular shaft assembly **3030** and the modular ultrasonic transducer assembly **3040** are attached to the modular handle assembly **3060**.

(631) Notably, in the above described aspects, the motor control circuit **726** (FIG. **36**) and/or the motor drive circuit **1165** (FIG. **50**) may be configured to attach/couple the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044** to a pre-desired torque. Such a pre-desired torque

may be a minimum torque adequate for the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044** to remain attached while the ultrasonic transducer **3054** excites the ultrasonic waveguide **3032** during operation of the device. Such a pre-desired torque would avoid damaging the ultrasonic transducer shaft **3044** and/or the ultrasonic waveguide **3032** (e.g., the threads, the chamfer, the sloped face, the receiving face, etc.). The motor control circuit **726** and/or the motor drive circuit **1165** may be configured to stop the motor **3004** from rotating the slip clutch gear **3020** (e.g., once the pre-desired torque is realized) despite the first shift switch **3504** being in an actuated state.

(632) Upon a successful coupling of the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044**, the first flange **3406** of the torque lever **3402** may be pivoted from the second point **3412** back to the first point **3410**. As the first flange **3406** of the torque lever **3402** is pivoted from the second point **3412** toward the first point **3410**, the transducer locking mechanism **3418** disengages from the ultrasonic transducer **3054** thereby releasing control of the ultrasonic transducer **3054** and the ultrasonic transducer shaft **3044**. Simultaneously, while the first flange **3406** of the torque lever **3402** is pivoted from the second point **3412** toward the first point **3410**, the shaft **3026** and the shifting spur gear **3012** are translated proximally so that the shifting spur gear **3012** can engage the primary drive gear **3016**. When the first flange **3406** of the torque lever **3402** reaches the first point **3410**, the shifting spur gear **3012** engages the primary drive gear **3016**. At the first point **3410**, the motor control circuit **726** (FIG. **36**) and/or the motor drive circuit **1165** (FIG. **50**) may be configured to rotate the primary drive gear **3016** via the shifting spur gear **3012** to perform shaft actuation functions such as clamping, rotation, and articulation (e.g., via a separate control(s) on the modular handle assembly **3060** as described herein). Notably, the primary drive gear **3016** may be configured to perform other desired shaft and/or end effector functions upon rotation (e.g., jaw closure).

(633) It should be appreciated that the above aspects also describe numerous structures to uncouple/decouple the ultrasonic waveguide **3032** of the modular shaft assembly **3030** and the ultrasonic transducer shaft **3044** of the modular ultrasonic transducer assembly **3040**. This is particularly useful when wishing to detach the modular shaft assembly **3030** and/or modular ultrasonic transducer assembly **3040** from the modular handle assembly **3060** (e.g., to attach another/different modular shaft assembly and/or modular ultrasonic transducer assembly). For example, the first flange **3406** of the torque lever **3402** may be pivoted from the first point **3410** to the second point **3412** such that movement of the ultrasonic transducer **3054** and ultrasonic transducer shaft **3044** is controlled via the transducer locking mechanism **3418** (e.g., rotation restricted while translation permitted) and the ultrasonic waveguide **3032** is rotatable relative to the ultrasonic transducer shaft **3044**. At this point, the motor control circuit **726** (FIG. **36**) and/or the motor drive circuit **1165** (FIG. **50**) may be configured to rotate the ultrasonic waveguide **3032** in the opposite direction (e.g., counterclockwise if left-handed threads, clockwise if right-handed threads) such that the ultrasonic waveguide **3032** unscrews from the ultrasonic transducer shaft **3044**. The modular shaft assembly **3030** and the modular ultrasonic transducer assembly **3040** can then be detached from the modular handle assembly **3060**.

(634) It should be appreciated that the above described aspects permit a single motor not only to perform conventional shaft and/or end effector functions (e.g., clamping, rotation, articulation, etc.) but also (i) to couple an ultrasonic waveguide **3032** of a modular shaft assembly **3030** to an ultrasonic transducer shaft **3044** of a modular ultrasonic transducer assembly **3040**, and (ii) to uncouple/decouple the ultrasonic waveguide **3032** of the modular shaft assembly **3030** from the ultrasonic transducer shaft **3044** of the modular ultrasonic transducer assembly **3040**. Such aspects permit a modular handheld surgical instrument to comprise numerous combinations of a modular handle assembly **3060**, a modular ultrasonic transducer assembly **3040** and a modular shaft assembly **3030**.

(635) FIGS. **117**, **118** and **121** depict example torqueing mechanisms for use in a device according

to an aspect of the present disclosure. As described above, when the shifting spur gear **3012** has been translated to the second position **3302** the teeth **3014** of the shifting spur gear **3012** meshingly engage the teeth **3022** of the slip clutch gear **3020**. Further, as described above, when the shifting spur gear **3012** is in the second position, the exterior shaft lock mechanism **3356**, **3358** may be withdrawn from the detent **3352**, **3354** in the exterior shaft **3038** (e.g., to uncouple the exterior shaft **3038** from the fixed external housing **3330**) to permit the exterior shaft **3038** to rotate.

(636) In one example aspect, the slip clutch gear **3020**, when rotated by the motor **3004** via the primary gear **3008** and the shifting spur gear **3012**, is configured to rotate the exterior shaft **3038** (FIG. **118**) which may include a first shaft portion **3314**, a second shaft portion **3316**, and a third shaft portion **3318** (FIG. **117**). The slip clutch gear **3020** is coupled to a proximal end of the first shaft portion **3314**. An internal surface at a proximal end of the second shaft portion **3316** may be fixedly attached to an external surface at a distal end of the first shaft portion **3314** and an internal surface at a distal end of the second shaft portion **3316** may be fixedly attached to an external surface at a proximal end of the third shaft portion **3318**. In one example aspect, the second shaft portion **3316** may be sized (e.g., longitudinal length, internal diameter, etc.) to enable the first internal shaft **3306** and the cylindrical coupler **3308** of the primary rotary drive **3304** to translate the second internal shaft **3310** distally and/or proximally (e.g., FIG. **117**).

(637) In line with above, the exterior shaft **3038** is coupled to the ultrasonic waveguide **3032** (e.g., via pins **3344**, **3346**) such that rotation of the exterior shaft **3038** rotates the ultrasonic waveguide **3032** relative to the ultrasonic transducer shaft **3044** (e.g., to couple the ultrasonic waveguide **3032** to the ultrasonic transducer shaft **3044** and/or to decouple the ultrasonic waveguide **3032** from the ultrasonic transducer shaft **3044**). In one aspect, such a coupling between the exterior shaft **3038** and the ultrasonic waveguide **3032** may occur distal of the second shaft portion **3316** of the exterior shaft **3038**. As previously indicated, the second internal shaft **3310** of the primary rotary drive **3304** may also rotate (e.g., via pins **3344**, **3346**) with the exterior shaft **3038** and the ultrasonic waveguide during the coupling and/or decoupling procedure. Notably however, since the shift spur gear **3012** is translated to the second position **3302** during the ultrasonic waveguide **3032** coupling and/or decoupling procedure, such rotation may simply result in negligible translation of the second internal shaft **3310** (e.g., translation permitted via the cutouts **3340**, **3342**) followed by free rotation of the cylindrical coupler **3308**, the first internal shaft **3306**, and the primary drive gear **3016**. Stated differently, since the shift spur gear **3012** is translated to the second position **3302**, the primary drive gear **3016** is able to rotate freely without damaging any device components.

(638) It should be appreciated that the shift clutch gear **3020** may rotate the exterior shaft **3038** to rotate the ultrasonic waveguide **3032** with respect to ultrasonic transducer shaft **3044** via clockwise and counter-clockwise rotation directions. Further, it should be appreciated that the exterior shaft **3038** may simply comprise the first shaft portion **3314**. In such an aspect, the shift clutch gear **3020** would rotate the first shaft portion **3314**, in a similar manner as described above, to rotate the ultrasonic waveguide **3032** with respect to the ultrasonic transducer shaft **3044** via clockwise and counter-clockwise rotation directions.

(639) FIGS. **117**, **118** and **121** depict an example mechanical aspect for controlling torque applied at the threaded interface between the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044** during the ultrasonic waveguide **3032** coupling and/or decoupling procedure. In one example, an interface (FIG. **117-118**, **3350**, FIG. **121**, **3440**) coupling the slip clutch gear **3020** to the first shaft portion **3314** of the exterior shaft **3038** may comprise a slip clutch subsystem **3442** (FIG. **121**). In one aspect of the slip clutch subsystem **3442**, an external surface at the proximal end of the first shaft portion **3314** (e.g., that interfaces an internal surface of slip clutch gear **3020**) may comprise a plurality of teeth extending radially outward **3444** and the internal surface of the slip clutch gear **3020** (e.g., that interfaces with the external surface at the proximal end of the first shaft portion **3314**) may comprise a plurality of teeth extending radially inward **3446**.

(640) Turning to FIG. **121**, the plurality of teeth **3444** associated with the first shaft portion **3314**

may be configured (e.g., via selected slope of the teeth, diameter measured at tips of the teeth, size of the teeth, resilient material of the teeth, etc.) to interface with the plurality of teeth **3446** associated with the slip clutch gear **3020** and the plurality of teeth **3446** associated with the slip clutch gear **3020** may be configured (e.g., via selected slope of the teeth, diameter measured at tips of the teeth, size of the teeth, resilient material of the teeth, etc.) to interface with the plurality of teeth **3444** associated with the first shaft portion **3314** such that when screwing (e.g., coupling) the ultrasonic waveguide **3032** onto the ultrasonic transducer shaft **3044**, the slip clutch gear **3020** and the first shaft portion **3020** remain fixedly coupled until a predefined threshold (e.g., desired maximum) torque is reached at the threaded interface between the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044**. Once the predefined threshold torque is reached, the slip clutch subsystem **3442** (e.g., via the teeth **3446** and the teeth **3444**) is configured to slip such that the slip clutch gear **3020** spins around the proximal end of the first shaft portion **3314** without further rotating the exterior shaft **3038** (e.g., or the ultrasonic waveguide **3032** coupled thereto). Larger torque thresholds may be achieved through teeth **3444/3446** comprising a steeper slope, a larger size, a greater coefficient of friction, and/or a larger amount of interference with opposing teeth and smaller torque thresholds may be achieved through teeth **3444/3446** comprising a smoother/shallower slope, a smaller size, a lesser coefficient of friction, and a smaller amount of interference with opposing teeth. It should be appreciated that combinations of such parameters may also be used to realize a desired maximum and/or limited torque threshold.

(641) In another aspect, the plurality of teeth **3444** associated with the first shaft portion **3314** may be configured (e.g., via selected slope of the teeth, diameter measured at tips of the teeth, size of the teeth, resilient material of the teeth, etc.) to interface with the plurality of teeth **3446** associated with the slip clutch gear **3020** and the plurality of teeth **3446** associated with the slip clutch gear **3020** may be configured (e.g., via selected slope of the teeth, diameter measured at tips of the teeth, size of the teeth, resilient material of the teeth, etc.) to interface with the plurality of teeth **3444** associated with the first shaft portion **3314** such that when unscrewing (e.g., decoupling) the ultrasonic waveguide **3032** from the ultrasonic transducer shaft **3044**, the slip clutch gear **3020** and the first shaft portion **3020** remain fixedly coupled until a predefined threshold (e.g., desired maximum) torque is reached. In various aspects, the slip clutch subsystem **3442** may be configured to slip at a higher predefined threshold when unscrewing (e.g., decoupling) the ultrasonic waveguide **3032** from the ultrasonic transducer shaft **3044** than when screwing (e.g., coupling) the ultrasonic waveguide **3032** onto/into the ultrasonic transducer shaft **3044** (e.g., two-way slip). In other various aspects, the slip clutch subsystem **3442** may be configured to not slip when unscrewing (e.g., decoupling) the ultrasonic waveguide **3032** from the ultrasonic transducer shaft **3044** (e.g., teeth **3446** associated with the slip clutch gear **3020** and the teeth **3444** associated with the first shaft portion **3314** meshingly engage without slippage) but may be configured to slip at a predefined threshold when screwing (e.g., coupling) the ultrasonic waveguide **3032** onto/into the ultrasonic transducer shaft **3044** (e.g., one-way slip).

(642) FIGS. **117** and **118** further represent alternative electrical aspects for controlling torque applied at the threaded interface between the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044** during the ultrasonic waveguide **3032** coupling and/or decoupling procedure. In one aspect, the slip clutch gear **3020** is fixedly attached to first shaft portion **3314**. As such, in lieu of the slip clutch subsystem **3442** described above, the motor control circuit **726** (FIG. **36**) and/or the motor drive circuit **1165** (FIG. **50**) may be configured (e.g., an electronic current limiter) to alter the current supplied to the motor **3004** such that the torque produced at the threaded interface between the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044** is limited to a predefined threshold (e.g., desired maximum) torque. In various aspects, the motor control circuit **726** and/or the motor drive circuit **1165** may be configured to alter the current supplied to the motor **3004** such that the torque produced at the threaded interface between the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044** is a higher predefined threshold when

unscrewing (e.g., decoupling) the ultrasonic waveguide **3032** from the ultrasonic transducer shaft **3044** than when screwing (e.g., coupling) the ultrasonic waveguide **3032** onto/into the ultrasonic transducer shaft **3044**. In other various aspects, the motor control circuit **726** and/or the motor drive circuit **1165** may be configured to deliver full current to the motor **3004** such that the torque produced at the threaded interface between the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044** is not electrically limited when unscrewing (e.g., decoupling) the ultrasonic waveguide **3032** from the ultrasonic transducer shaft **3044** but may be configured to alter the current supplied to the motor **3004** such that the torque produced at the threaded interface between the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044** is limited to a predefined threshold torque when screwing (e.g. coupling) the ultrasonic waveguide **3032** onto/into the ultrasonic transducer shaft **3044**.

(643) Turning to FIGS. **123-125**, proper torque may be verified by a combination of motor torque measurements and an ultrasonic ping that returns a known good reflection profile. In view of FIG. **123**, the motor control circuit **726** and/or the motor drive circuit **1165** may be configured to cut off current **3602** supplied to the motor **3004** when a predefined torque limit **3605** is reached. In view of FIG. **124**, the motor control circuit **726** and/or the motor drive circuit **1165** may be configured to limit current supplied to the motor **3004** based on the function being performed. For example, torqueing the ultrasonic waveguide **3032** onto/into the ultrasonic transducer shaft **3044** (FIG. **124**, **3604**) may be limited to a first current limit **3606**, rotating the shaft and/or end effector (FIG. **124**, **3608**, e.g., distal roll) may be limited to a second current limit **3610**, articulating the shaft and/or end effector (FIG. **124**, **3612**) may be limited to a third current limit **3614**, and/or clamping the end effector (FIG. **124**, **3616**, e.g. constant force clamp arm) may be limited to a fourth current limit **3618**. FIG. **125** illustrates the motor assembly **3620** comprising the motor **3004**, the shaft **3006**, and the primary gear **3008** as previously discussed herein. In FIG. **125**, the motor assembly **3620** may further comprise a planetary gear box **3622**, a first magnet **3624** and a second magnet **3626** fixedly attached coaxially about the shaft **3006**, a wire coiled around the shaft **3628** positioned within the first and second magnets, and a strain gauge **3630** including a microchip (not shown). In one aspect, the coiled wire **3628** rotates with the shaft **3006** within the first and second magnets **3624**, **3626** to power the strain gauge **3630**. The strain gauge **3630** is configured to measure the torque applied by the motor **3004** via the planetary gear box **3622**. In one aspect, the motor control circuit **726** and/or the motor drive circuit **1165** may be configured to electronically limit the current supplied to the motor **3004** based on the torque measured via the strain gauge **3630**.

(644) In an alternative aspect, a combination of mechanical aspects (e.g., slip clutch subsystem **3442**) and electrical aspects (e.g., altering the motor **3004** current via the motor control circuit **726** and/or the motor drive circuit **1165**) is contemplated for controlling torque applied at the threaded interface between the ultrasonic waveguide **3032** and the ultrasonic transducer shaft **3044** during the ultrasonic waveguide **3032** coupling and/or decoupling procedure.

(645) In one aspect, the present disclosure provides a surgical instrument, comprising: a modular handle assembly, comprising: a motor assembly comprising a motor and a motor gear; and a shift gear translatable between a first position and a second position; a modular ultrasonic transducer assembly coupled to the modular handle assembly, wherein the modular ultrasonic transducer assembly comprises: an ultrasonic transducer; and an ultrasonic transducer shaft extending distally from the ultrasonic transducer; and a modular shaft assembly coupled to the modular ultrasonic transducer assembly and the modular handle assembly, wherein the modular shaft assembly comprises: a first rotatable shaft extending distally along a shaft axis, wherein the first rotatable shaft comprises a drive gear; an ultrasonic waveguide coaxially aligned with the first rotatable shaft about the shaft axis; and a second rotatable shaft coaxially aligned with the first rotatable shaft and the ultrasonic waveguide about the shaft axis, wherein the second rotatable shaft comprises a torque gear; wherein when the shift gear is translated to the first position, the motor gear is configured to rotate the drive gear via the shift gear, and wherein when the shift gear is translated to

the second position, the motor gear is configured to rotate the torque gear via the shift gear. The shift gear may be manually or electronically translatable between the first position and the second position.

(646) The drive gear upon rotation may be operable to perform at least one shaft actuation function comprising one or more than one of clamping, rotating, or articulating an actuation device. The torque gear upon rotation may be operable to couple the ultrasonic waveguide to the ultrasonic transducer shaft or decouple the ultrasonic waveguide from the ultrasonic transducer shaft. The torque gear upon rotation may be operable to controllably torque the ultrasonic waveguide to the ultrasonic transducer shaft. The torque gear may be coupled to the second rotatable shaft via a slip-clutch subsystem, wherein the slip-clutch subsystem is configured such that the torque gear and the second rotatable shaft remain fixedly coupled until a predefined torque is reached and such that the torque gear slips about the second rotatable shaft after the predefined torque is reached to controllably torque the ultrasonic waveguide to the ultrasonic transducer shaft. The slip-clutch subsystem may be further configured such that the torque gear slips about the second rotatable shaft at a higher predefined torque when decoupling the ultrasonic waveguide from the ultrasonic transducer shaft.

(647) The surgical instrument may further comprise a motor circuit, wherein the motor circuit is configured to alter current supplied to the motor to controllably torque the ultrasonic waveguide to the ultrasonic transducer shaft. The surgical instrument may further comprise a strain gauge configured to measure torque applied by the motor, and wherein the motor circuit is configured to limit current supplied to the motor based on the torque measured by the strain gauge.

(648) In another aspect, the present disclosure provides a modular handheld surgical instrument, comprising: a motor assembly comprising a motor and a motor gear; a shift gear translatable distally and proximally between a first position and a second position; a transducer assembly comprising an ultrasonic transducer shaft; and a shaft assembly, comprising: a first shaft extending distally along a shaft axis, wherein the first shaft comprises a drive gear; an ultrasonic waveguide coaxially aligned inside the first shaft about the shaft axis; and a second shaft coaxially aligned outside the first shaft and the ultrasonic waveguide about the shaft axis, wherein the second shaft comprises a torque gear coupled to the second shaft via a slip-clutch subsystem, wherein the slip-clutch subsystem is configured such that the torque gear does not slip about the second shaft until a predefined torque is reached to controllably torque the ultrasonic waveguide to the ultrasonic transducer shaft; wherein when the shift gear is translated to the first position, the motor gear is configured to rotate the drive gear via the shift gear, and wherein when the shift gear is translated to the second position, the motor gear is configured to rotate the torque gear via the shift gear.

(649) The drive gear upon rotation may be operable to perform at least one shaft actuation function comprising one or more than one of clamping, rotating, or articulating an actuation device. The torque gear upon rotation may be operable to couple the ultrasonic waveguide to the ultrasonic transducer shaft or decouple the ultrasonic waveguide from the ultrasonic transducer shaft. The slip-clutch subsystem may be further configured such that the torque gear slips about the second shaft at a higher predefined torque when decoupling the ultrasonic waveguide from the ultrasonic transducer shaft. The slip-clutch subsystem may be further configured such that the torque gear does not slip about the second shaft when decoupling the ultrasonic waveguide from the ultrasonic transducer shaft. The shift gear may be manually or electronically translatable between the first position and the second position.

(650) In another aspect, the present disclosure provides a modular handheld surgical instrument, comprising: a motor assembly comprising a motor and a motor gear; a shift gear translatable distally and proximally between a first position and a second position; a transducer assembly comprising an ultrasonic transducer shaft; and a shaft assembly, comprising: a first shaft extending distally along a shaft axis, wherein the first shaft comprises a drive gear; an ultrasonic waveguide coaxially aligned inside the first shaft about the shaft axis; and a second shaft coaxially aligned

outside the first shaft and the ultrasonic waveguide about the shaft axis, wherein the second shaft comprises a torque gear; and a motor circuit, wherein the motor circuit is configured to alter current supplied to the motor to controllably torque the ultrasonic waveguide to the ultrasonic transducer shaft via the torque gear; wherein when the shift gear is translated to the first position, the motor gear is configured to rotate the drive gear via the shift gear, and wherein when the shift gear is translated to the second position, the motor gear is configured to rotate the torque gear via the shift gear.

(651) The first shaft may be selectively coupleable to at least two independent actuation devices, and wherein the drive gear upon rotation is operable to actuate the at least two independent actuation devices. The modular handheld surgical instrument may further comprise a strain gauge configured to measure torque applied by the motor, and wherein the motor circuit is configured to limit current supplied to the motor based on the torque measured by the strain gauge. The motor circuit may be configured to alter current supplied to the motor such that the torque when coupling the ultrasonic waveguide to the ultrasonic transducer shaft does not exceed a predefined torque. The motor circuit may be configured to alter current supplied to the motor such that the torque when decoupling the ultrasonic waveguide from the ultrasonic transducer shaft is a higher predefined torque.

Modular Battery Powered Handheld Surgical Instrument with a Plurality of Control Programs

(652) In another aspect, the present disclosure provides, a modular battery powered handheld surgical instrument with a plurality of control programs. A battery powered modular surgical instrument includes a control handle assembly with a processor coupled to a memory, a shaft assembly operably coupled to the control handle assembly and detachable therefrom. The shaft assembly includes circuit modules and a memory. The control programs are configured to operate the circuit modules. The control programs include computer executable instructions. The instrument also includes a transducer assembly operably coupled to the control handle assembly and detachable therefrom. The transducer assembly includes a memory and a transducer configured to convert a drive signal to mechanical vibrations. The control programs are configured to control the conversion of the drive signal to mechanical vibrations. The instrument also includes a battery assembly operably coupled to the control handle assembly and detachable therefrom. The battery assembly comprises a memory and is configured to power the surgical instrument.

(653) FIGS. **62, 63, and 126-131** describe aspects of the present disclosure. In one aspect, the subject matter comprises a segmented circuit design for any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-70** to enable a plurality of control programs to operate in a plurality of different shaft assemblies **110, 490, 510, 1110, 1210**, transducer assemblies **104, 486, 504**, knife drive assemblies **1104, 1152, 1204**, and/or battery assemblies **106, 484, 506, 1106, 1206**, where the plurality of the control programs may reside in the different assemblies and are uploaded to the handle assembly **102, 482, 502, 1102, 1201** when attached thereto. FIGS. **126-131** describe aspects of the present disclosure. In one aspect, the subject matter of the present disclosure comprises controlling the operation of a battery operated modular surgical instrument **100, 480, 500, 600, 1100, 1150, 1200** as described herein in connection with FIGS. **1-70** with a plurality of control programs. The battery operated modular surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** comprise components such as a handle assembly **102, 482, 502, 1102, 1202** comprising a controller, a shaft assembly **110, 490, 4510, 110, 1210**, a transducer assembly **104, 486, 504**, a knife drive assembly **1104, 1152, 1204**, and/or a battery assembly **106, 484, 506, 1106, 1206**.

(654) In various aspects, the battery powered modular surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** as described herein in connection with FIGS. **1-70** further comprise an end effector **112, 492, 512, 1000, 1112, 1212** and some aspects comprise a motor assembly **1160, 1260**. The components of the modular surgical instrument are modular components that may be combined into a single modular component. For example, a proximal end of the shaft can be

attached to the handle assembly such that the shaft assembly and the handle assembly are operably coupled to form a single modular component. Each of the plurality of control programs comprise machine executable instructions that may be executed by a processor of the modular surgical instrument. Although the processor is generally located either in the handle assembly or the battery assembly, in various aspects the processor may be located in any modular component such as the shaft assembly, transducer assembly, and/or the knife drive assembly. Executing a control program corresponding to a modular component controls the operation of the modular component by, for example, causing the modular component such as an ultrasonic shaft assembly to apply ultrasonic energy for a surgical application or procedure in accordance with the operation algorithm embodied in the executed control program. The modular surgical instrument is configured to treat patient tissue in surgical applications or procedures involving the application of a particular energy modality. Energy modalities can include ultrasonic energy, combination of ultrasonic and high-frequency current (e.g., RF) energy, high-frequency current energy with I-blade knife configuration, or a high-frequency current energy and opposable jaw with knife, for example. (655) FIG. 126 is a system schematic diagram illustrating components of a battery powered modular surgical instrument **2400**, such as the battery operated modular surgical instruments **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. 1-70, according to various aspects of the present disclosure. The components include a transducer assembly **2402**, a control handle assembly **2404**, a shaft assembly **2406**, and a battery assembly **2408**. The transducer assembly **2402** comprises a modular transducer that may be configured to implement a particular operation of the surgical instrument **2400**. For example, the modular transducer assembly **2402** may be an ultrasonic transducer operating at a 31 kHz resonant frequency or an ultrasonic transducer operating at a 55 kHz resonant frequency. Therefore, a user of the surgical instrument **2400** may select a modular variation of the transducer assembly **2402** for operation of the modular surgical instrument. A subset of a plurality of control programs embodies an algorithm, protocol or procedure corresponding to an operation or a function of the transducer assembly **2402**. For example, the subset of control programs can correspond to operation of the transducer assembly **2402** at 31 kHz or 51 kHz frequency.

(656) In various aspects, the ultrasonic transducer component of the ultrasonic transducer assembly **2402** receives electrical power through an ultrasonic electrical signal from a generator via for example, a cable. The ultrasonic transducer converts the received electrical power into ultrasonic vibration energy. The operation of the ultrasonic transducer is described herein in connection with FIGS. 1-15. The transducer assembly **2402** is operably coupled to the control handle assembly **2404** via a pair of connectors **2420a**, **2420b**, such as a male coupler and a corresponding female socket coupler. The transducer assembly **2402** comprises an ultrasonic transducer, drive circuitry, and a memory device **2410**. The memory device **2410** may be a volatile memory device or a nonvolatile memory device such as a random-access memory (RAM), dynamic RAM (DRAM), synchronous (SDRAM), read-only memory (ROM) erasable programmable ROM (EPROM), electrically EPROM (EEPROM), flash memory or other suitable memory device. In some aspects, the memory device **2414** is a plurality of nonvolatile memory devices, volatile memory device, a combination, or a sub-combination thereof. In various aspects, the memory device **2410** stores a main RTOS of the modular surgical instrument. Operation of the main RTOS is described in commonly owned U.S. Patent Application Publication No. 2016/0074038, now U.S. Pat. No. 9,730,695, which is incorporated herein by reference in its entirety.

(657) In some aspects, the memory device **2410** stores all or a subset of control programs corresponding to the operation of the selected modular variant of the ultrasonic transducer. For example, executing an ultrasonic transducer control program by a processor can control the ultrasonic transducer by causing the ultrasonic transducer to convert an ultrasonic drive signal into a particular mode of vibration such as longitudinal, flexural, torsional and harmonics thereof. An ultrasonic transducer control program also can be configured to control the operation of the

ultrasonic transducer by monitoring the rate at which the ultrasonic transducer converts a drive signal into vibrations based on monitored characteristics such as ultrasonic transducer tissue impedance. Alternatively or additionally, in various aspects, an ultrasonic transducer control program may be configured to operate a plurality of circuit modules such as software, programs, data, drivers, and/or application program interfaces (APIs). The ultrasonic transducer assembly **2402** comprises a plurality of circuit modules and the circuit modules control the operation of the ultrasonic transducer. As further described with reference to FIGS. **127-131** control programs corresponding to the ultrasonic transducer may comprise component identification, RTOS update, usage counter, energy update, 55 kHz, 31 kHz, and RF control programs, or any combination or sub-combination thereof. In some aspects, the memory device **2410** stores a plurality of control programs each corresponding to an operation or a function of the ultrasonic transducer. In other aspects, multiple control programs in conjunction correspond to an operation or a function of the ultrasonic transducer. In various aspects, the transducer assembly **2402** comprises a processor coupled to the memory device **2410**.

(658) The control handle assembly **2404** is operably coupled via the pair of connectors **2420a**, **2420b** to the transducer assembly **2402**. The control handle assembly **2404** is operably coupled to the shaft assembly **2406** via a pair of connectors **2422a**, **2422b** such as a male coupler and a corresponding female socket coupler. The control handle assembly **2404** is operably coupled to the battery assembly **2408** via a pair of connectors **2424a**, **2424b** such as a male coupler and a corresponding female socket coupler. The control handle assembly **2404** is a modular control handle that may be, for example, a control handle configured to support a particular drive system of the surgical instrument such as a rotatable drive shaft assembly **2406** configured to advance an end effector of the surgical instrument such as a stapler, cutting member or another type of end effector for other types of surgical instruments, graspers, clip appliers, access device, drug/gene therapy devices, ultrasound, RF, and or laser devices. In some aspects, the control handle assembly **2404** may comprise a closure trigger that is configured to transition between an unactuated position and an actuated position. The unactuated position corresponds to an open or unclamped configuration of the shaft assembly **2406** and the actuated position corresponds to a closed or clamped configuration of the shaft assembly **2406**. A user of the surgical instrument may control the actuation of the closure trigger. In various aspects, the control handle assembly **2404** may comprise a plurality of handle housing segments that may be connected by for example, screws, snap features, or adhesive to form a handle grip such as a pistol grip. In some aspects, the control handle assembly **2404** comprises a motor.

(659) The control handle assembly **2404** comprises a processor **2412** coupled to a memory device **2414**. The processor **2412** and the memory device **2414** may be integrated into a single integrated circuit (IC) or multiple ICs. The processor **2412** may be a microprocessor, a programmable gate-array (PGA), an application-specific IC (ASIC), controller, microcontroller, digital signal processor (DSP), programmable logic device (PLD) or a combination or sub-combination thereof. The memory device **2414** may be a volatile memory device or a nonvolatile memory device such as a RAM, DRAM, SDRAM, ROM, EPROM, EEPROM, flash memory, or other suitable memory device. In some aspects, the memory device **2414** is a plurality of nonvolatile memory devices, volatile memory device, a combination, or a sub-combination thereof. In various aspects, the memory device **2414** stores the main RTOS **2502** of the modular surgical instrument. In some aspects, the control handle assembly **2404** comprises one or more primary controllers. In various aspects, the control handle assembly **2404** also comprises one or more safety controllers. More generally, the modular control handle assembly **2404** operably supports a plurality of drive systems that are configured to generate and apply various control motions to corresponding portions of the modular shaft assembly **2406**. For example, the control handle assembly **2404** may comprise a handle assembly comprising an elongate body, a proximal end, a distal end, and a cavity configured to accept another component of the modular surgical instrument. Therefore, a user of the modular

surgical instrument may select a modular variation of the control handle assembly **2404** to support a patient treatment operation of the modular surgical instrument. A modular variation can correspond to a particular control program of the plurality of control programs. In some aspects, the memory device **2414** stores a plurality of control programs each corresponding to an operation or a function of the control handle assembly **2404**. In other aspects, multiple control programs in conjunction correspond to an operation or a function of the control handle assembly **2404**.

(660) Different modular variations of the control handle assembly **2404** may be configured to support the application of a particular energy modality. A subset of a plurality of control programs embodies an algorithm, protocol, or procedures corresponding to an operation or a function of the control handle assembly **2404**. For example, a control program of the plurality of control programs can correspond to operation of a control handle assembly **2404** configured to apply RF energy opposable jaw. In some aspects, the memory device **2414** stores a subset of control programs corresponding to the operation or function of the selected modular variant of the control handle assembly **2404**. For example, executing a control handle control program by the processor **2412** can control the control handle assembly **2404** by causing the control handle assembly **2404** to actuate a shaft assembly of the shaft assembly **2406**. Alternatively or additionally, in various aspects, the control handle assembly **2404** comprises a plurality of circuit modules such as software, programs, data, drivers, and/or application program interfaces (APIs) to control the operation of the control handle assembly **2404**. The plurality of circuit modules may be implemented by one or more hardware components, e.g., processors, DSPs, PLDs, ASICs, circuits, registers and/or software components, e.g., programs, subroutines, logic and/or combinations of hardware and software components. In various aspects, a control handle control program may be configured to operate the plurality of circuit modules. For example, executing a control handle control program by the processor **2412** may operate a handle motor circuit module by applying the control motions generated by a motor of the modular surgical instrument to actuate the shaft assembly **2406**. As further described with reference to FIGS. **127-129**, control programs corresponding to the control handle assembly **2404** may comprise RTOS software, motor control, switch, safety control, RTOS update, and energy update control programs, or any combination or sub-combination thereof. Control programs corresponding to the control handle assembly **2404** may further comprise the control programs corresponding to the transducer assembly **2402** and the shaft assembly **2406**. Transducer control programs include 55 kHz, 31 kHz, and RF control programs. Shaft assembly **2406** control programs include ultrasonic, RF I-blade, RF opposable jaw, and combination ultrasonic and RF control programs, for example.

(661) The shaft assembly **2406** is operably coupled via connectors **2422a**, **2422b** such as a male coupler and a corresponding female socket coupler, to the control handle assembly **2404**. In various aspects, the shaft assembly **2406** is operably connected to an end effector of the modular surgical instrument to perform one or more surgical procedures. The shaft assembly **2406** may comprise an articulation joint and an articular lock that are configured to detachably hold the end effector in a particular position. Operation of the articulation joint and articular lock is described in commonly owned U.S. Patent Application Publication No. 2014/0263541, which is incorporated herein by reference in its entirety. The shaft assembly **2406** is a modular shaft comprising modular variations of shaft assemblies that may be, for example, configured to be coupled to a particular end effector of the surgical instrument such as an ultrasonic blade. In various aspects, the shaft assembly **2406** may comprise an interchangeable shaft assembly that is configured for removable attachment via for example, a latch, from a housing of the modular surgical instrument. The shaft assembly of the shaft assembly **2406** also may include a spine configured to support a shaft frame, a firing member, and a closure tube extending around the spine. The shaft assembly may support axial travel of the firing member within the spine of the shaft assembly **2406**. The shaft assembly of the shaft assembly **2406** also may comprise a slip ring assembly configured to conduct electric power between the shaft assembly **2406** and the end effector. The operation of interchangeable shaft

assemblies of the shaft assembly **2406** is further described in commonly owned U.S. Patent Application Publication No. 2015/0272579, now U.S. Pat. No. 9,743,929, which is incorporated herein by reference in its entirety. Modular variations of shaft assemblies of the shaft assembly **2406** are configured to be actuated by various corresponding drive systems of the modular surgical instrument.

(662) The shaft assembly **2406** comprises a memory device **2416**. The memory device **2416** may be a volatile memory device or a nonvolatile memory device such as a RAM, DRAM, SDRAM, ROM, EPROM, EEPROM, flash memory, or other suitable memory device. In some aspects, the memory device **2416** is a plurality of nonvolatile memory devices, volatile memory device, a combination, or a sub-combination thereof. In various aspects, the memory device **2416** stores the main RTOS of the modular surgical instrument. In various aspects, the shaft assembly **2406** comprises a processor coupled to the memory device **2416** that may be integrated into a single IC or multiple ICs. The processor may be a microprocessor, a PGA, an ASIC, controller, microcontroller, DSP, PLD or a combination or sub-combination thereof. In some aspects, the memory device **2416** stores a plurality of control programs each corresponding to a function or an operation of the control handle assembly **2404**. In other aspects, multiple control programs in conjunction correspond to an operation or a function of the control handle assembly **2404**. Modular variations of shaft assemblies of the shaft assembly **2406** may be configured to be operably coupled to modular variations of end effectors in accordance with a selected energy modality or an operation modality of the modular surgical instrument. Moreover, modular variations of drive systems of the modular surgical instrument may be configured to generate and apply at least one control motion to actuate modular variations of shaft assemblies in accordance with a selected energy modality or an operation modality of the modular surgical instrument. Therefore, a user of the modular surgical instrument may select a modular variation of the shaft assembly **2406** based on for example, shaft assemblies configured to apply other motions and forms of energy such as, for example, high-frequency current (e.g., RF) energy, ultrasonic energy and/or motion to end effector arrangements adapted for use in connection with various surgical applications and procedures.

(663) Different modular variations of the shaft assembly **2406** can correspond to particular control programs of the plurality of control programs. A subset of a plurality of control programs embodies an algorithm, protocol or procedure corresponding to an operation of the shaft assembly **2406**. For example, a control program of the plurality of control programs can correspond to a shaft assembly configured to be operably coupled to an end effector applying a combination of ultrasonic and RF energy. In some aspects, the memory device **2416** stores all or a subset of control programs corresponding to the operation or the function of the selected modular variant of the shaft assembly **2406**. For example, executing a shaft attachment control program can enable the actuation of a latch actuator assembly to actuate a lock yoke. Alternatively or additionally, in various aspects, the shaft assembly **2406** comprises a plurality of circuit modules such as software, programs, data, drivers, and/or application program interfaces (APIs) to control the operation of the shaft assembly **2406**. The plurality of circuit modules may be implemented by one or more hardware components, e.g., processors, DSPs, PLDs, ASICs, circuits, registers and/or software components, e.g., programs, subroutines, logic and/or combinations of hardware and software components. In various aspects, a shaft control program may be configured to operate the plurality of circuit modules. For example, a shaft attachment control program may operate a shaft attachment circuit module by causing the latch actuator assembly to cooperate with the lock yoke to couple the shaft assembly **2406** to the control handle assembly **2404**. As further described with reference to FIGS. **127-129**, control programs corresponding to the shaft assembly **2406** may comprise component identification, RTOS update, usage counter, energy update, or any combination or sub-combination thereof. The component identification control program may comprise specific component identification control programs such as ultrasonic, RF I-blade, RF opposable jaw, and combination

ultrasonic and RF component identification control programs.

(664) The battery assembly **2408** is operably coupled via connectors **2424a**, **2424b** such as a male coupler and a corresponding female socket coupler, to the control handle assembly **2404**. The battery assembly **2408** comprises a Lithium-ion (“Li”), other suitable battery or a plurality thereof that may be connected in series. In some aspects, the battery assembly **2408** may be a battery such as the 14.4 volt nickel metal hydride (NiMH) SmartDriver Battery, available from MicroAire Surgical Instruments, Charlottesville, VA. The battery assembly **2408** is configured to provide power for the operation of the modular surgical instrument. Specifically, the battery assembly **2408** is rechargeable and applies voltage to components of the modular surgical instrument, including for example, an electric motor. In various aspects, the voltage polarity applied to the electric motor by the battery assembly **2408** is reversible between a clockwise polarity and a counterclockwise polarity. The applied voltage may operate the electric motor to drive a drive member to effectuate an end effector of the modular surgical instrument. In various aspects, the battery assembly **2408** is a component of a power assembly of the modular surgical instrument. The battery assembly **2408** comprises a memory device **2418**. In some aspects, the battery assembly **2408** further comprises a processor. The memory device **2418** may be a volatile memory device or a nonvolatile memory device such as a RAM, DRAM, SDRAM, ROM, EPROM, EEPROM, flash memory, or other suitable memory device. In some aspects, the memory device **2418** is a plurality of nonvolatile memory devices, volatile memory device, a combination, or a sub-combination thereof. In various aspects, the memory device **2418** stores the main RTOS of the modular surgical instrument. In various aspects, the battery assembly **2408** comprises a processor coupled to the memory device **2418** that may be integrated into a single IC or multiple ICs. The processor may be a microprocessor, a PGA, an ASIC, controller, microcontroller, DSP, PLD or a combination or sub-combination thereof.

(665) Modular variations of the battery assembly **2408** may be configured to power modular variations of end effectors in accordance with a selected energy modality or an operation modality of the modular surgical instrument. For example, differences in the voltage rating of modular battery variants **2408** can correspond to different end effectors configured to achieve an effect according to a selected surgical procedure or operation, including endocutter, grasper, cutter, stapler, clip applier, access device, drug/gene therapy delivery device, and energy delivery device using an ultrasonic, RF I-blade, RF opposable jaw, combination ultrasonic or RF energy modality. Different modular variants of the battery assembly **2408** can correspond to particular control programs of the plurality of control programs. A subset of a plurality of control programs embodies an algorithm, protocol or procedure corresponding to an operation or function of the battery assembly **2408**. For example, a control program of the plurality of control programs can correspond to a battery assembly **2408** configured to provide power to a modular surgical instrument configured to apply an ultrasonic energy modality. In some aspects, the memory device **2418** stores all or a subset of control programs corresponding to the operation or the function of the selected modular variant of the battery assembly **2408**. In some aspects, the memory device **2418** stores a plurality of control programs each corresponding to an operation or a function of the control handle assembly **2404**. In other aspects, multiple control programs in conjunction correspond to an operation or a function of the control handle assembly **2404**. For example, executing a power management control program can enable a power management controller of the modular surgical instrument to modulate the power output of the battery in accordance with predetermined power requirements, such as the power requirements of an attached shaft assembly.

(666) Alternatively or additionally, in various aspects, the battery assembly **2408** comprises a plurality of circuit modules such as software, programs, data, drivers, and/or application program interfaces (APIs) to control the operation of the battery assembly **2408**. The plurality of circuit modules may be implemented by one or more hardware components, e.g., processors, DSPs, PLDs, ASICs, circuits, registers and/or software components, e.g., programs, subroutines, logic and/or

combinations of hardware and software components. In various aspects, a battery control program may be configured to operate the plurality of circuit modules. For example, a battery charge monitoring control program may operate a charge monitoring circuit module by causing a controller communicating with the memory device **2418** and a state of charge monitoring circuit to measure the state of charge of the battery assembly **2408**. The controller may further compare the measured state of charge with any charge values previously stored in the memory device **2418** and display the measured value of the state of charge on an LCD screen of the modular surgical instrument, as described, for example, in U.S. Patent Application Publication No. 2016/0106424, which is incorporated herein by reference. As further described with reference to FIGS. **127-129**, control programs corresponding to the battery assembly **2408** may comprise maximum number of uses, charge and drainage, RTOS update, usage counter, energy update, motor control, RTOS software, switch, safety control programs or any combination or sub-combination thereof. Control programs corresponding to the battery assembly **2408** may further comprise the control programs corresponding to the transducer assembly **2402** and the shaft assembly **2406**. Ultrasonic transducer control programs include 55 kHz, 31 kHz, and RF control programs. Shaft control programs include ultrasonic, RF I-Blade, RF opposable jaw, and combination ultrasonic and RF control programs.

(667) FIGS. **127-129** describe pluralities of control programs **2500**, **2600**, **2700** distributed between the transducer assembly **2402**, control handle assembly **2404**, shaft assembly **2406**, and battery assembly **2408**. FIG. **127** describes a distribution of pluralities of control programs **2500** according to one aspect of the present disclosure in which the memory device **2414** of the control handle assembly **2404** stores a plurality of control programs **2500** comprising base operating control programs corresponding to the general operation of the modular surgical instrument, according to one aspect of the present disclosure. Moreover, the memory device **2414** stores a plurality of control programs **2500** comprising base operating control programs corresponding to transducer and shaft modalities corresponding to energy modalities of the modular surgical instrument. The memory devices **2412**, **2416**, **2418** store pluralities of control programs wherein each plurality of the pluralities of control programs corresponds to a function or operation of the respective specific component of the modular surgical instrument such as the transducer assembly **2402**, shaft assembly **2406**, and battery assembly **2408**. In some aspects, the memory device **2414** stores a basic input/output system (BIOS) program that is configured to control the communication between the processor **2412** and the modular components of the modular surgical instruments.

(668) During operation of the modular surgical instrument, the BIOS program loads the component identification **2528** control program to the memory device **2414** for the processor **2412** to execute. Execution of the component identification **2524** control program enables the processor **2412** to select the corresponding one or more of the transducer **2509** base operating control programs **2510**, **2512**, **2514** for the BIOS to load to the memory device **2414**. The BIOS also loads the component identification **2532** control program to the memory device **2414** for the processor **2412** to execute. Execution of the component identification **2532** control program enables the processor **2412** to select the corresponding one or more of the shaft **2515** base operating control programs **2516**, **2518**, **2520**, **2522** for the BIOS to load to the memory device **2414**. The processor **2412** can then execute the control programs in the memory device **2414** to implement the selected modular variants of the modular shaft assembly **2406** and transducer assembly **2402**. If any of the modular components of the modular surgical instrument have an updated version of the RTOS software **2502** stored in their respective memory devices **2412**, **2416**, **2418**, the processor **2404** may download the updated version to the memory device **2414** via the respective RTOS update **2528**, **2536**, **2546** control programs.

(669) The plurality of base operating control programs corresponding to general operation comprise the RTOS software **2502**, motor control **2504**, switch control **2506**, and safety control **2508** control programs. The plurality of base operating control programs corresponding to the

transducer control programs **2509** and shaft control programs **2515** comprise 55 kHz, 31 kHz, or RF control programs **2510**, **2512**, **2514**, respectively, for the transducer assembly **2402** and ultrasonic **2516**, combination ultrasonic and RF **2518**, RF I-Blade **2520**, and RF opposable jaw **2522** control programs for the shaft assembly **2406**. In various aspects, the memory device **2414** comprises a nonvolatile memory device such as ROM and a volatile memory device such as RAM. The BIOS program may be stored in the nonvolatile memory device and also may contain addresses of the modular components. The RTOS software **2502** is configured to control the execution, by the processor **2412**, of the pluralities of control programs distributed between components of the modular surgical instrument. In some aspects, the RTOS software **2502** is stored in the nonvolatile memory. When the modular surgical instrument powers up, the BIOS program of the modular surgical instrument loads the RTOS software **2502** from the nonvolatile memory device to the volatile memory device.

(670) The motor control **2504** comprises an algorithm, protocol or procedure to control operation of a motor of the modular surgical instrument, such as by controlling a direction of rotation. In some aspects, the motor control **2504** is configured to determine the direction of the motor by determining the polarity of the voltage applied by the battery assembly **2408**. The switch control **2506** comprises an algorithm, protocol or procedure to control operation of an end effector of a motor of the modular surgical instrument, such as by controlling the direction of articulating the end effector. The direction may be clockwise or counterclockwise. In various aspects, the switch control **2506** is configured to control whether a switch is in a closed or an open position, wherein a closed position may activate the motor to articulate the end effector in a particular direction. The safety control **2508** comprises an algorithm, protocol or procedure to control operation of a safety controller that is configured to perform safety critical applications such as by interrupting power to the motor if an error or fault condition is detected by the safety controller.

(671) The 55 kHz control program **2510** comprises an algorithm, protocol or procedure to control operation of an ultrasonic transducer portion of the transducer assembly **2402** that converts received electrical power into ultrasonic vibration energy at a resonant frequency of 55 kHz. The 31 kHz control program **2512** comprises an algorithm, protocol or procedure to control operation of an ultrasonic transducer portion of the transducer assembly **2402** that converts received electrical power into ultrasonic vibration energy at a resonant frequency of 31 kHz. The RF control program **2514** comprises an algorithm, protocol or procedure to control the delivery of high-frequency current (e.g., RF) energy to an end effector to facilitate the application of RF energy by the modular surgical instrument **2400**. The ultrasonic control program **2516** comprises an algorithm, protocol or procedure to control operation of an ultrasonic waveguide located within the shaft assembly **2406** that is configured to apply ultrasonic energy for a surgical procedure or operation. The combination ultrasonic and RF control program **2518** comprises an algorithm, protocol or procedure to control operation of a shaft assembly **2406** that is configured to apply either ultrasonic or RF energy for a surgical procedure or operation. The RF I-blade control program **2520** comprises an algorithm, protocol or procedure to control operation of a shaft assembly **2406** that is configured to apply RF energy to an end effector with a cutting member such as an I-blade, for a surgical procedure or operation. The RF opposable jaw control program **2522** comprises an algorithm, protocol or procedure to control operation of a shaft assembly **2406** that is configured to apply RF energy via an end effector comprising opposable jaw members, for a surgical procedure or operation.

(672) A plurality of control programs **2500** corresponding to the transducer assembly **2402** comprise the component identification **2524**, usage counter **2526**, RTOS update **2528**, and energy update **2530** control programs. The component identification **2524** comprises an algorithm, protocol or procedure to identify the modular variant of the transducer assembly **2402** to the BIOS and RTOS programs. For example, the component identification **2524** may identify an ultrasonic transducer as a 55 kHz transducer. The usage counter **2526** comprises an algorithm, protocol or procedure to monitor the usage of the ultrasonic transducer. For example, the usage counter **2526**

can maintain a usage cycle count corresponding to the number of instances that the ultrasonic transducer is used by a user of the modular surgical instrument. In some aspects, if the usage cycle count value calculated by the usage counter **2526** exceeds a predetermined value, the processor **2412** may disable the transducer assembly **2402** or disable the entire modular surgical instrument from performing an operation or function. The RTOS update control program **2528** comprises an algorithm, protocol or procedure to identify whether the memory device **2410** stores an update to the RTOS software **2502** stored in the memory device **2414**.

(673) In various aspects, a user of the modular surgical instrument may upload an updated version of the RTOS software **2502** via, for example, a computer coupled to the memory device **2410** through a transmission media, to the memory device **2410**. When the modular transducer assembly **2402** is attached to the modular surgical instrument, the updated version stored in the memory device **2410** is downloaded by the processor **2412** to be stored in the memory device **2414**. The updated version may overwrite the existing version of the RTOS software **2502** stored in the memory device **2414**. The energy update **2530** comprises an algorithm, protocol or procedure to identify whether the memory device **2410** stores an update to a surgical procedure energy algorithm stored in the memory device **2414**. The surgical procedure energy algorithm comprises one or more techniques to employ one or more energy modalities based on tissue parameters such as the type of tissue to be treated in the surgical procedure and tissue impedance. For example, a particular surgical procedure energy algorithm involves applying RF energy for a portion of the surgical procedure, ultrasonic energy for a second portion, and a combination of RF and ultrasonic energy for a third portion in accordance with a particular surgical procedure. An update to a surgical procedure energy algorithm comprises a change to an existing surgical energy algorithm. Such a change may be, for example, increasing the frequency at which RF energy is applied for a portion of the surgical procedure in order to perform the procedure at an improved level of precision and control. In various aspects, a user of the modular surgical instrument may upload the update to a surgical procedure energy algorithm the memory device **2410** that the processor may download and store in the memory device **2414**.

(674) The plurality of control programs corresponding to the shaft assembly **2406** comprises the component identification **2532**, the usage counter **2534**, the RTOS update **2536**, and the energy update **2538**. The component identification **2532** comprises an algorithm, protocol or procedure to identify the modular variant of the shaft assembly **2406** to the BIOS and RTOS programs, such as a shaft assembly **2406** configured to apply ultrasonic energy. The usage counter **2534** comprises an algorithm, protocol or procedure to monitor the usage of the shaft assembly **2406**. As described previously in connection with usage counter **2526**, the usage counter **2534** can maintain a usage cycle count. As described previously in connection with RTOS update **2528**, the RTOS update **2536** comprises an algorithm, protocol or procedure to identify whether the memory device **2416** stores an updated version of the RTOS software **2502**. As described previously in connection with energy update **2530**, the energy update **2538** comprises an algorithm, protocol or procedure to identify whether the memory device **2416** stores an updated version of a surgical procedure energy algorithm.

(675) A plurality of control programs **2500** corresponding to the battery assembly **2408** comprises usage counter **2540**, maximum number of uses **2542**, charge and drainage **2544**, RTOS update **2546**, and energy update **2548**. The usage counter **2540** comprises an algorithm, protocol or procedure to monitor the usage of the battery assembly **2408**. As described previously in connection with usage counter **2526** and usage counter **2534**, the usage counter **2540** can maintain a usage cycle count. The maximum number of uses **2542** comprises an algorithm, protocol or procedure to determine a maximum usage value. In some aspects, if the usage cycle count exceeds the maximum usage value, the processor **2412** may disable the battery assembly **2408** or disable the entire modular surgical instrument from performing an operation or function. The charge and drainage **2544** comprises an algorithm, protocol or procedure to control charging and draining a

rechargeable battery assembly **2408**. In various aspects, a dedicated drainage circuit may implement the power drain function of the charge and drainage **2544** control program. A state of charge monitoring circuit may implement the recharge function of the charge and drainage **2544** control program. In some aspects, the state of charge monitoring circuit may measure the current state of charge, compare the current state with a previously stored state in the memory device **2418**, and display the measured or previously stored value on an LCD screen. As described previously in connection with RTOS update **2528** and RTOS update **2536**, the RTOS update **2546** comprises an algorithm, protocol or procedure to identify whether the memory device **2418** stores an updated version of the RTOS software **2502**. As described previously in connection with energy update **2530** and energy update **2538**, the energy update **2548** comprises an algorithm, protocol or procedure to identify whether the memory device **2418** stores an updated version of a surgical procedure energy algorithm.

(676) FIG. **128** describes a distribution of pluralities of control programs **2600** according to one aspect of the present disclosure in which the memory device **2418** of the battery assembly **2408** stores a plurality of control programs **2500** comprising base operating control programs corresponding to the general operation of the modular surgical instrument, according too one aspect of the present disclosure. Moreover, the memory device **2418** stores a plurality of control programs **2500** comprising base operating control programs corresponding to transducer and shaft modalities corresponding to energy modalities of the modular surgical instrument. The memory device **2418** also stores a plurality of control programs **2500** corresponding to functions or operations of the battery assembly **2408**. The memory devices **2412**, **2416** store pluralities of control programs wherein each plurality of the pluralities of control programs corresponds to a function or operation of the respective specific component of the modular surgical instrument such as the transducer assembly **2402** and shaft assembly **2406**. The processor **2412** is located in the battery assembly **2408** instead of the control handle assembly **2404**. In some aspects, the processor **2412** is still located in the control handle assembly **2404** and the battery assembly **2408** comprises another processor.

(677) In some aspects, the memory device **2418** stores the BIOS program that is configured to control the communication between the processor **2412** and the modular components of the modular surgical instruments. During operation of the modular surgical instrument, the BIOS program loads the component identification **2602** control program to the memory device **2418** for the processor **2412** to execute. Execution of the component identification **2602** control program enables the processor **2412** to select the corresponding one or more of the ultrasonic transducer base operating control programs **2510**, **2512**, **2514** for the BIOS to load to the memory device **2418**. The BIOS also loads the component identification **2532** control program to the memory device **2418** for the processor **2412** to execute. Execution of the component identification **2532** control program enables the processor to select the corresponding one or more of the shaft base operating control programs **2516**, **2518**, **2520**, **2522** for the BIOS to load to the memory device **2418**. The processor **2412** can then execute the control programs in the memory device **2418** to implement the selected modular variants of the modular shaft assembly **2406** and transducer assembly **2402**. In various aspects, the memory device **2418** comprises a nonvolatile memory device and a volatile memory device. The BIOS program may be stored in the nonvolatile memory device and also may contain addresses of the modular components. In some aspects, the RTOS software **2502** is stored in the nonvolatile memory of the memory device **2418**. The RTOS software **2502** is configured to control the execution, by the processor **2412**, of the pluralities of control programs distributed between components of the modular surgical instrument. The BIOS program of the modular surgical instrument can load the RTOS software **2502** from the nonvolatile memory device to the volatile memory device when the modular surgical instrument powers up.

(678) As described in connection with FIG. **127**, the plurality of base operating control programs corresponding to general operation comprise the RTOS software **2502**, the motor control **2504**, the

switch control **2506**, and the safety control **2508**. As described in connection with FIG. **127** base operating control programs corresponding to transducer and shaft modalities comprise the 55 kHz, the 31 kHz, and the RF control programs **2510**, **2512**, **2514**, respectively, for the transducer assembly **2402** and ultrasonic control program **2516**, combination ultrasonic and RF control program **2518**, the RF I-blade control program **2520**, and the RF opposable jaw control program **2522** control programs for the shaft assembly **2406**. As described in connection with FIG. **127**, control programs corresponding to functions or operations of the battery assembly **2408** comprise usage counter **2610**, maximum number of uses **2612**, charge and drainage **2614**, and energy update **2616**. Usage counter **2610**, maximum number of uses **2612**, charge and drainage **2614**, and energy update **2616** each comprise an algorithm, protocol or procedure that is substantially the same as usage counter **2540**, maximum number of uses **2542**, charge and drainage **2544**, and energy update **2548**.

(679) In the distribution of pluralities of control programs **2600** according to the aspect of FIG. **128**, the plurality of control programs **2600** corresponding to the control handle assembly **2404** comprise the plurality of base operating control programs corresponding to general operation and the plurality of base operating control programs corresponding to transducer control programs **2509** and shaft control programs **2515** modalities. Therefore, the memory device **2414** does not store any of the pluralities of control programs. The plurality of control programs **2600** corresponding to a function or operation of the transducer assembly **2402** comprises the component identification **2602** and usage counter **2604**. The component identification **2602** and the usage counter **2604** each comprise an algorithm, protocol or procedure that is substantially the same as the component identification **2528** and the usage counter **2530**. The plurality of control programs **2600** corresponding to a function or operation the shaft assembly **2406** comprises the component identification **2606** and usage counter **2608**. The component identification **2606** and usage counter **2608** each comprise an algorithm, protocol or procedure that is substantially the same as the component identification **2536** and the usage counter **2538**.

(680) FIG. **129** describes a distribution of pluralities of control programs **2700** according to one aspect of the present disclosure in which the memory device **2414** stores a plurality of control programs **2700** comprising base operating control programs corresponding to the general operation of the modular surgical instrument, according too one aspect of the present disclosure. The memory device **2410** stores a plurality of control programs **2700** comprising base operating control programs corresponding to transducer control programs **2509** modalities corresponding to energy modalities of the modular surgical instrument. The memory device **2416** stores a plurality of control programs **2700** comprising base operating control programs corresponding to shaft modalities corresponding to energy modalities of the modular surgical instrument. Therefore, the control handle assembly **2404** stores the general operation base operating control programs, while the transducer assembly **2402** and the shaft assembly **2406** store their respective energy modality base operating control programs. The memory devices **2412**, **2414**, **2416**, **2418** also store pluralities of control programs **2700** wherein each plurality of the pluralities of control programs **2700** corresponds to a function or operation of the respective specific component of the modular surgical instrument such as the transducer assembly **2402**, control handle assembly **2404**, shaft assembly **2406**, and battery assembly **2408**.

(681) In some aspects, the memory device **2418** stores the BIOS program that is configured to control the communication between the processor **2412** and the modular components of the modular surgical instruments. During operation of the modular surgical instrument, the BIOS program loads the component identification **2704** control program to the memory device **2414** for the processor **2412** to execute. Execution of the component identification **2704** control program enables the processor **2412** to select the corresponding one or more of the transducer base operating control programs **2510**, **2512**, **2514** for the BIOS to load to the memory device **2414**. The BIOS also loads the component identification **2712** control program to the memory device **2414** for the

processor **2412** to execute. Execution of the component identification **2532** control program enables the processor to select the corresponding one or more of the shaft base operating control programs **2516, 2518, 2520, 2522** for the BIOS to load to the memory device **2414**. The processor **2412** can then execute the control programs in the memory device **2414** to implement the selected modular variants of the modular shaft assembly **2406** and transducer assembly **2402**. In various aspects, the memory device **2414** comprises a nonvolatile memory device and a volatile memory device. The BIOS program may be stored in the nonvolatile memory device and also may contain addresses of the modular components.

(682) In some aspects, the RTOS software **2502** is stored in the nonvolatile memory of the memory device **2414**. The RTOS software **2502** is configured to control the execution, by the processor **2412**, of the pluralities of control programs distributed between components of the modular surgical instrument. In some aspects, one or more of the transducer assembly **2402**, shaft assembly **2406** and the battery assembly **2408** comprises one or more additional processors. As described in connection with FIGS. **127** and **128**, the plurality of base operating control programs **2600, 2700** corresponding to general operation comprise the RTOS software **2502**, the motor control **2504**, the switch control **2506**, and the safety control **2508**. As described in connection with FIGS. **127** and **128**, base operating control programs **2600, 2700** corresponding to transducer and shaft modalities comprise the 55 kHz **2510**, the 31 kHz **2512**, and the RF **2514** control programs for the transducer assembly **2402** and ultrasonic control programs **2516**, combination ultrasonic and the RF, the RF I-blade, and the RF opposable jaw control programs **2518, 2520, 2522** for the shaft assembly **2406**. In the distribution of the plurality of control programs **2700** according to the aspect of FIG. **129**, the plurality of control programs **2700** corresponding to a function or operation of the control handle assembly **2404** comprise the energy update **2702**. The energy update **2702** control program comprises an algorithm, protocol or procedure to identify whether the memory device **2414** stores an update to an existing surgical procedure energy algorithm stored in the memory device **2414**. The plurality of control programs corresponding to a function or operation of the transducer assembly **2402** comprise the component identification **2704**, RTOS update **2706**, usage counter **2708**, and energy update **2710** control programs. The component identification **2704**, RTOS update **2706**, usage counter **2708**, and energy update **2710** control programs each comprise an algorithm, protocol or procedure that is substantially the same as the component identification **2524**, RTOS update **2528**, usage counter **2526**, and energy update **2530** control programs.

(683) The plurality of control programs **2700** corresponding to a function or operation of the shaft assembly **2406** comprise component identification **2712**, RTOS update **2714**, usage counter **2716**, and energy update **2718** control programs. The component identification **2712**, RTOS update **2714**, usage counter **2716**, and energy update **2718** control programs each comprise an algorithm, protocol or procedure that is substantially the same as the component identification **2532**, RTOS update **2536**, usage counter **2534**, and energy update **2538** control programs. The plurality of control programs corresponding to a function or operation of the battery assembly **2408** comprise usage counter **2720**, maximum number of uses **2722**, charge and drainage **2724**, RTOS update **2726**, and energy update **2728** control programs. The usage counter **2720**, maximum number of uses **2722**, charge and drainage **2724**, RTOS update **2726**, and energy update **2728** control programs each comprise an algorithm, protocol or procedure that is substantially the same as the usage counter **2540**, maximum number of uses **2542**, charge and drainage **2544**, RTOS update **2546**, and energy update **2548** control programs.

(684) FIG. **130** is a logic diagram **2800** of a process for controlling the operation of a battery assembly operated modular surgical instrument with a plurality of control programs, according to one aspect of the present disclosure. With reference to FIGS. **126, 127** and **131**, at the outset, the processor **2412** identifies **2802** a plurality of control programs. Each of the plurality of control programs **2500, 2600, 2700** (FIGS. **127-129**), for example, comprise computer executable instructions that may be executed by the processor **2412**. In various aspects, the processor **2412**

comprises a primary controller and a safety controller. As previously described, in various aspects, some of the plurality of control programs may be configured to operate a plurality of circuit modules of the shaft assembly **2406**. Some of the plurality of control programs also may be configured to control the conversion of a drive signal to mechanical vibrations. The drive signal may be an electrical drive signal. The plurality of control programs may be stored in the memory devices **2410**, **2414**, **2416**, **2418** by the processor **2412** according to a predetermined distribution. For example, as described partially with reference to FIG. **127**, one example predetermined distribution may be that the memory device **2414** stores the RTOS software **2502** and motor control **2504** control programs of the plurality of control programs, the memory device **2410** stores the component identification **2524** and usage counter **2526** control programs of the plurality of control programs, the memory device **2416** stores the RTOS update **2536** and energy update **2538** control programs of the plurality of control programs, and the memory device **2418** stores the maximum number of uses **2542** and charge and drainage **2544** control programs of the plurality of control programs. In some aspects, each of the memory devices **2410**, **2414**, **2416**, **2418** may be a nonvolatile memory device or a volatile memory device. In other aspects, each of the memory devices **2410**, **2414**, **2416**, **2418** may comprise both a nonvolatile memory device and a volatile memory device.

(685) After identifying **2802** the control programs, the processor **2412** determines **2804** the subset of the plurality of control programs necessary to operate the modular surgical instrument based on a desired operation of the modular surgical instrument. For example, a subset of the plurality of control programs may be necessary to operate the plurality of circuit modules of the shaft assembly **2406**. The processor **2412** selects **2806** at least one of the plurality of control programs to implement operation of the modular surgical instrument.

(686) In various aspects, one of the memory devices **2410**, **2414**, **2416**, **2418** is a nonvolatile memory device storing at least one of the plurality of control programs. Selecting **2806** the at least one control program by the processor **2412** comprises the processor **2412** downloading the at least one control program from the nonvolatile memory device to a volatile memory device located in the control handle assembly **2404**, shaft assembly **2406**, transducer assembly **2402**, or battery assembly **2408**. When the selected at least one control program is stored in the volatile memory device, the processor **2412** executes **2808** the selected at least one control program. The processor **2412** may continue to select **2806** and execute **2808** selected control programs continuously during operation of the modular surgical instrument.

(687) As previously described, the processor **2412** may store **2810** the plurality of control programs according to a predetermined distribution. In various aspects, the control handle assembly **2404**, shaft assembly **2406**, transducer assembly **2402**, or battery assembly **2408** may comprise additional processors in addition to the processor **2412**. The additional processors may be secondary processors. In some aspects, the processor **2412** may download **2812** a first, second, and third subset of the plurality of control programs stored respectively within the memory devices **2410**, **2416**, **2418** according to the predetermined distribution to the memory device **2414**. In other aspects, the predetermined distribution is the memory device **2414** storing each of the plurality of control programs. In some aspects, the predetermined distribution is the memory device **2414** storing the base operating control programs corresponding to the general operation of the modular surgical instrument, as described in FIG. **72**. The memory device **2414** may also store base operating control programs corresponding to transducer assembly and shaft assembly modalities corresponding to energy modalities of the modular surgical instrument, as described in FIG. **127**. In other aspects, the memory device **2410** stores the base operating control programs corresponding to transducer assembly modalities corresponding to energy modalities of the modular surgical instrument. The memory device **2416** stores the base operating control programs corresponding to shaft assembly modalities corresponding to energy modalities of the modular surgical instrument.

(688) The processor **2412** identifies **2814** the modular variants of the components of the modular

surgical instrument to be used by a user of the modular surgical instrument. A modular variant may be, for example, a modular shaft assembly **2406** comprising rotary shaft control or a modular transducer assembly **2402** comprising a transducer operating at 31 kHz resonant frequency. The processor **2412** determines **2816** the corresponding control programs of the plurality of control programs that correspond to the identified modular variants. The processor **2412** selects **2818** the corresponding subset of the plurality of control programs based on a look-up table. For example, the processor **2412** may select a base operating control program corresponding to a transducer assembly modality such as the 55 kHz **2510** control program if the modular variant of the modular transducer is a transducer operating at 55 kHz resonant frequency. Similarly, the processor **2412** may select a base operating control program corresponding to a shaft assembly modality such as the RF I-blade **2520** control program if the modular variant of the modular shaft is a modular shaft configured to implement a RF I-blade energy modality. The look-up table may comprise an indication that the selected subset of the plurality of control programs corresponds to at least one of the shaft assembly **2406** or the transducer assembly **2402**. In some aspects, the processor **2402** may determine **2816** the control programs corresponding to the identified modular variants based on the look-up table. After selecting **2818** the corresponding subset of control programs, the processor **2412** may execute the subset of control programs. The process of the logic diagram **2800** terminates **2820**.

(689) FIG. **131** is a logic diagram **2900** of a process for controlling the operation of a battery assembly operated modular surgical instrument with a plurality of control programs, according to one aspect of the present disclosure. With reference to FIGS. **126**, **127** and **131**, at the outset, a user of the modular surgical instrument attaches the detachable modular components together such that the modular components of the modular surgical instrument are operably coupled together. For example, in various aspects, the user attaches **2902** a shaft assembly **2406** to the control handle assembly **2404** to operably couple the shaft assembly **2406** to the control handle assembly **2404**. A proximal end of the shaft assembly **2406** may be attached to the control handle assembly **2404**. The user attaches **2904** the transducer assembly **2402** to the control handle assembly **2404** to operably couple the transducer assembly **2402** to the control handle assembly **2404**. For example, a distal end of the transducer assembly **2402** may be attached to a proximal end of the control handle assembly **2404**. The user attaches **2906** the battery assembly **2408** to the control handle assembly **2404** to operably couple the battery assembly **2408** to the control handle assembly **2404**. As previously described, a plurality of control programs may be stored in the memory devices **2410**, **2414**, **2416**, **2418** by the processor **2412** according to a predetermined distribution. After the shaft assembly **2406**, transducer assembly **2402**, and battery assembly **2408** are each attached to the control handle assembly **2404**, the processor **2402** determines and identifies **2908** the plurality of control programs according to the predetermined distribution. In various aspects, the processor **2420** is alternatively located in one of the shaft assembly **2406**, transducer assembly **2402**, or battery assembly **2408**. The identified plurality of control programs stored according to the predetermined distribution in the memory devices **2410**, **2414**, **2416**, **2418** may be uploaded to a volatile memory device located in the control handle assembly **2404**, shaft assembly **2406**, transducer assembly **2402**, or battery assembly **2408**. In aspects, one of the memory devices **2410**, **2414**, **2416**, **2418** may comprise the volatile memory device. For example, the memory device **2414** may comprise the volatile memory device.

(690) In some aspects, each of the memory devices **2410**, **2414**, **2416**, **2418** each stores a subset of the plurality of control programs according to the predetermined distribution. For example, the processor **2412** may determine and identify **2908** a first subset of the plurality of control programs in memory device **2414**, a second subset of the plurality of control programs in memory device **2416**, a third subset of the plurality of control programs in memory device **2410**, and a fourth subset of the plurality of control programs in memory device **2418**. In aspects, the first subset of the plurality of control programs comprises the plurality of base operating control programs

corresponding to general operation such as the motor control **2504** and switch control **2506** control programs. Each of the first, second, third and fourth subsets of the plurality of control programs may be uploaded to the volatile memory device located in the control handle assembly **2404**, shaft assembly **2406**, transducer assembly **2402**, or battery assembly **2408**, as previously described. In various aspects, after the user attaches new modular variants of each of the transducer assembly **2402**, shaft assembly **2406**, and battery assembly **2408** to a previously used control handle assembly **2404**, a second plurality of control programs is stored in the memory devices corresponding to the attached new modular variants of the transducer assembly **2402**, shaft assembly **2406**, and battery assembly **2408** according to a second predetermined distribution. The new modular variants may be a new modular variant manufactured from a factory. In some aspects, the second plurality of control programs comprises different versions of the plurality of control programs.

(691) Therefore, after the new modular variants are attached, the processor **2412** determines **2910** whether any of the second plurality of control programs are updated versions of the corresponding control program of the plurality of control programs. The updated control programs may correspond to a previous version of the updated control program stored in the memory device **2414**. For example, the memory device of a new modular transducer assembly may store an updated version of the 55 kHz control program **2510**. The memory device **2414** may have stored a previous version of the 55 kHz control program **2510**. Thus, the processor **2412** may determine **2910** that the 55 kHz control program **2510** is an updated version and upload the updated version to the memory device **2414**. In general, if the processor **2412** determines **2910** that at least one of the second plurality of control programs is an updated version corresponding to a previous version stored in the memory device **2414**, the processor **2412** uploads **2912** the updated version of the at least one control program to the memory device **2414**. The processor **2412** deletes **2914** the previous version of the at least one control program previously stored in the memory device **2414**. If the processor **2412** determines **2910** that the at least one of the second plurality of control programs is not an updated version, the processor **2412** does not upload **2912** the updated version.

(692) The processor **2412** selects **2916** at least one of the plurality of control programs or second plurality of control programs to implement operation of the modular surgical instrument, as previously described in connection with FIG. **130**. As previously described in FIG. **130**, the processor **2412** downloads the at least one control program from the corresponding nonvolatile memory device to a volatile memory device. The processor **2412** may select **2916** based on a look-up table. As previously described, when the selected at least one control program is stored in the volatile memory device, the processor **2412** executes **2918** the selected at least one control program. The processor **2412** may continue to select **H616** and execute **H618** selected control programs continuously during operation of the modular surgical instrument. In various aspects, the processor **2412** may write usage data to the memory device of the corresponding modular component of selected control programs. For example, the processor **2412** may write **2920** time of usage data to the memory devices **2410**, **2416**, **2418** of the transducer assembly **2402**, shaft assembly **2406**, and battery assembly **2408** based on executing the usage counter **2526**, usage counter **2534**, usage counter **2540** control programs, respectively. For another example, the processor **2412** may write motor usage data to the memory device **2414** based on executing the motor control **2504** control program. In aspects, the processor **2412** may write data to the memory device **2416** such as time in use, maximum force, and shaft error data as well as control handle assembly **2404**, transducer assembly **2402**, and battery assembly **2408** serial number data. The processor **2412** also may write data to the memory device **2410** such as time in use, index of number of re-uses, error data as well as shaft assembly **2406**, control handle assembly **2404**, and battery assembly **2408** serial number data. The processor **2412** also may write data to the memory device **2418** such as number of rechargeable uses, end effector functional data, error data, and battery discharge data.

(693) The processor **2412** determines **2922** whether any of the attached transducer assembly **2402**, shaft assembly **2406**, and battery assembly **2408**, or whether the control handle assembly **2404** has an updated version of the main RTOS or BIOS program. If the processor **2412** determines **2922** that there is an updated version of the main RTOS or BIOS program, the processor **2412** updates **2924** the main RTOS or BIOS program based on the updated version stored in the corresponding memory device **2410**, **2414**, **2416**, **2418**. If the processor **2412** determines **2922** that there is not an updated version of the main RTOS or BIOS program, the processor **2412** does not update **2924**. The process of the logic diagram **2900** terminates **2926**.

(694) In one aspect, the present disclosure provides a battery powered modular surgical instrument, comprising: a control handle assembly comprising a processor coupled to a first memory device; a shaft assembly having a proximal end operably coupled to the control handle assembly and detachable from the control handle assembly, wherein the shaft assembly comprises a plurality of circuit modules and a second memory device, wherein a plurality of control programs is configured to operate the plurality of circuit modules, wherein each of the plurality of control programs comprises computer executable instructions; a transducer assembly operably coupled to the control handle assembly and detachable from the control handle assembly, wherein the transducer assembly comprises a third memory device and comprises a transducer that is configured to convert a drive signal to mechanical vibrations, wherein the plurality of control programs is configured to control the conversion of the drive signal to mechanical vibrations; a battery assembly operably coupled to the control handle assembly and detachable from the control handle assembly, wherein the battery assembly comprises a fourth memory device and the battery assembly is configured to power the modular surgical instrument.

(695) The processor may comprise a primary controller and a safety controller. The plurality of control programs may be stored according to a predetermined distribution between the first memory device, second memory device, third memory device, or fourth memory device. The first memory device, second memory device, third memory device, or fourth memory device may be a nonvolatile memory device storing at least one control program of the plurality of control programs, wherein the processor is configured to download the at least one control program to a volatile memory device located in the control handle assembly, shaft assembly, transducer assembly, or battery assembly.

(696) The processor may be configured to select at least one of the plurality of control programs based on a look-up table. The look-up table may comprise an indication that the selected at least one of the plurality of control programs corresponds to at least one of the shaft assembly or the transducer assembly. The plurality of control programs may comprise any one of a component identification program, a usage counter program, a real-time operating system (RTOS) program, an energy update program, and/or a motor control program.

(697) The surgical instrument may further comprise an end effector coupled to a distal end of the shaft assembly; a motor positioned in the control handle assembly and configured to operate the end effector, wherein the motor control program is configured to control the operations of the motor. The processor may be a first processor, wherein one of the shaft assembly, transducer assembly or battery assembly comprises a second processor.

(698) In another aspect, the present disclosure provides a method to operate a battery powered modular surgical instrument, comprising: a control handle assembly comprising a processor coupled to a first memory device, a shaft assembly having a proximal end operably coupled to the control handle assembly and detachable from the control handle assembly, wherein the shaft assembly comprises a plurality of circuit modules and a second memory device, wherein a plurality of control programs is configured to operate the plurality of circuit modules, wherein each of the plurality of control programs comprises computer executable instructions, a transducer assembly operably coupled to the control handle assembly and detachable from the control handle assembly, wherein the transducer assembly comprises a third memory device and comprises a transducer that

is configured to convert a drive signal to mechanical vibrations, wherein at least one of the plurality of control programs is configured to control the conversion of the drive signal to mechanical vibrations, and a battery assembly operably coupled to the control handle assembly and detachable from the control handle assembly, wherein the battery assembly comprises a fourth memory device and the battery assembly is configured to power the modular surgical instrument, wherein the method comprises the steps of: identifying, by the processor, the plurality of control programs; selecting, by the processor, at least one of the plurality of control programs; executing, by the processor, at least one of the plurality of control programs.

(699) The processor may comprise a primary controller and a safety controller, the method may further comprise executing at least one of the plurality of control programs by the primary controller and the safety controller. The method may comprise storing, by the processor, the plurality of control programs according to a predetermined distribution between the first memory device, second memory device, third memory device, or fourth memory device. The first memory device, second memory device, third memory device, or fourth memory device may be a nonvolatile memory device storing at least one control program of the plurality of control programs, the method further comprising: downloading, by the processor, the at least one control program to a volatile memory device located in the control handle assembly, shaft assembly, transducer assembly, or battery assembly. The method may further comprising: identifying, by the processor, a modular variant of one or more of the shaft assembly or transducer assembly; selecting, by the processor, the at least one control program based on determining that the at least one control program corresponds to the identified modular variant based on a look-up table.

(700) In another aspect, the present disclosure provides a method to operate a battery powered surgical instrument, comprising: a control handle assembly comprising a processor coupled to a first memory device, a shaft assembly detached from the control handle assembly, wherein the shaft assembly comprises a plurality of circuit modules and a second memory device, wherein a plurality of control programs is configured to operate the plurality of circuit modules, wherein the plurality of control programs is stored in the first memory device, wherein each of the plurality of control programs comprises computer executable instructions, a transducer assembly detached from the control handle assembly, wherein the transducer assembly comprises a third memory device and comprises a transducer that is configured to convert a drive signal to mechanical vibrations, wherein at least one of the plurality of control programs is configured to control the conversion of the drive signal to mechanical vibrations, and a battery assembly detached from the control handle assembly, wherein the battery assembly comprises a fourth memory device and the battery assembly is configured to power the modular surgical instrument, wherein the method comprises the steps of: attaching, by a user of the surgical instrument, a proximal end of the shaft assembly to the control handle assembly to operably couple the shaft assembly to the control handle assembly; attaching, by the user of the surgical instrument, the transducer assembly to a distal end of the shaft assembly to operably couple the transducer assembly to the control handle assembly; attaching, by the user of the surgical instrument, the battery assembly to the control handle assembly to operably couple the battery assembly to the control handle assembly; selecting, by the processor, at least one of the plurality of control programs based on a look-up table; executing, by the processor, the at least one of the plurality of control programs.

(701) The plurality of control programs may be a first plurality of control programs, the method may further comprise determining, by the processor, that a second plurality of control programs is stored according to a predetermined distribution between the second memory device, third memory device, or fourth memory device; uploading, by the processor, at least one of second plurality of control programs to the first memory device. The at least one second plurality of control programs may be an updated version of at least one of the first plurality of control programs, the method may further comprise deleting, by the processor, at least one of the first plurality of control programs from the first memory device. The plurality of control programs may

be a first plurality of control programs, wherein the first plurality of control programs comprises a motor control program and a switch program, the method may further comprise identifying, by the processor, a second plurality of control programs stored in the second memory device; identifying, by the processor, a third plurality of control programs stored in the third memory device; identifying, by the processor, a fourth plurality of control programs stored in the fourth memory device.

(702) The method may further comprise writing, by the processor, shaft assembly usage data to the second memory device based on executing, by the processor, at least one of the second plurality of control programs; writing, by the processor, transducer assembly usage data to the third memory device based on executing, by the processor, at least one of the third plurality of control programs; writing, by the processor, battery assembly usage data to the fourth memory device based on executing, by the processor, at least one of the fourth plurality of control programs. The method may further comprise writing, by the processor, usage data to the first memory device based on executing, by the processor, at least one of the second plurality of control programs.

Modular Battery Powered Handheld Surgical Instrument with Energy Conservation Techniques

(703) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with energy conservation techniques. Disclosed is a method of conserving energy in a surgical instrument that includes a segmented circuit having a plurality of independently operated circuit segments, a voltage control circuit, an energy source, a memory, and a processor coupled to the memory. The processor is configured to control a state of a circuit segment of the plurality of circuit segments. The state can be an energized state or a deenergized state. The method includes transmitting an energizing signal from the processor to a voltage control circuit, receiving the energizing signal by the voltage control circuit to apply a voltage to a circuit segment of the plurality of circuit segments, applying the voltage to the circuit segment by the voltage control circuit to cause the circuit segment to transition from the deenergized state to the energized state in accordance with an energization sequence that is different from a deenergization sequence.

(704) FIGS. **62**, **63**, and **132-135** describe aspects of the present disclosure. In one aspect, the subject matter comprises a segmented circuit design for any one of the surgical instruments **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-70** to enable selectively powering individual circuit segments of a segmented circuit. The selective powering may be achieved in a controlled manner according to an energy conservation method. The controlled manner may include executing an energization sequence or a deenergization sequence by the segmented circuit. The energization sequence may be different from a deenergization sequence. In a non-use state of the surgical instrument, such as when there are no users using the surgical instrument, energy conservation is realized by executing an energization sequence that is different from a deenergization sequence. The selective powering technique according to the present disclosure enables verification of each of the plurality of circuit segments according to a power management mode before powering the circuit segments. The power management mode is further described below with reference to FIG. **132**. The surgical instrument may be a segmented modular mixed energy surgical instrument that enables control and customization of the surgical instrument. In various aspects, the surgical instrument may comprise a shaft, a handle, a transducer, a battery, a motor, and an end effector, as previously described in connection with FIGS. **1-70**

(705) With reference back to FIG. **62**, there is illustrated the components of a control circuit **1300** of a surgical instrument, according to one aspect of the present disclosure. The control circuit **1300** comprises a processor **1302** coupled to a volatile memory **1304**, one or more sensors **1306**, a non-volatile memory **1308** and a battery **1310**. The surgical instrument may comprise a handle housing to house the control circuit **1300** and to contain general purpose controls to implement the power conservation mode further described in FIG. **132**. In general, the processor **1302** is electrically coupled to each of the plurality of circuit segments of the segmented circuit **1401** as illustrated in

FIG. 63 to activate or deactivate the circuit segments in accordance with energization and deenergization sequences such as the example sequences described in FIGS. 132, 133, and 135. (706) FIG. 63 is a system diagram 1400 of a segmented circuit 1401 comprising a plurality of independently operated circuit segments 1402, 1414, 1416, 1420, 1424, 1428, 1434, 1440, according to one aspect of the present disclosure. One or more sensors 1306 may include an accelerometer to verify the function or operation of each of the plurality of circuit segments, based on a safety check and a Power On Self Test (POST) further described in connection with FIG. 71. The battery 1310 powers the surgical instrument by providing a source voltage that causes a current. The battery 1310 may comprise the motor control circuit segment block 1428 illustrated in FIG. 63.

(707) In the aspect shown in FIG. 133, the plurality of circuit segments start first in the standby mode, transition second to the sleep mode, and transition third to the operational mode. However, in other aspects, the plurality of circuit segments may transition from any one of the three modes to any other one of the three modes. For example, the plurality of circuit segments may transition directly from the standby mode to the operational mode. Each individual circuit segment may be placed in a particular state by the voltage control circuit 1408 based on the execution by the processor 1302 of machine executable instructions. The states comprise a deenergized state, a low energy state, and an energized state. The deenergized state corresponds to the sleep mode, the low energy state corresponds to the standby mode, and the energized state corresponds to the operational mode. Transition to the low energy state may be achieved by, for example, the use of a potentiometer.

(708) As further described with reference to FIG. 133, the plurality of circuit segments may transition from the sleep mode or the standby mode to the operational mode in accordance with an energization sequence. The plurality of circuit segments also may transition from the operational mode to the standby mode or the sleep mode in accordance with a deenergization sequence. The energization sequence and the deenergization sequence may be different. In some aspects, the energization sequence comprises energizing only a subset of circuit segments of the plurality of circuit segments. In some aspects, the deenergization sequence comprises deenergizing only a subset of circuit segments of the plurality of circuit segments.

(709) Referring back to the system diagram 1400 in FIG. 63, the segmented circuit 1401 comprises a plurality of circuit segments comprising a transition circuit segment 1402, a processor circuit segment 1414, a handle circuit segment 1416, a communication circuit segment 1420, a display circuit segment 1424, a motor circuit segment 1428, an energy treatment circuit segment 1434, and a shaft circuit segment 1440. The transition circuit segment comprises a wake up circuit 1404, a boost current circuit 1406, a voltage control circuit 1408, a safety controller 1410 and a POST controller 1412. The transition circuit segment 1402 is configured to implement a deenergization and an energization sequence, a safety detection protocol, and a POST. The voltage control circuit 1408 may also comprise a processor and memory device, as illustrated in FIG. 134.

(710) FIG. 132 is a logic diagram 2000 of a process for controlling the operation of a surgical instrument according to the energy conservation method comprising the POST and operation verification, according to one aspect of the present disclosure. The logic diagram 2000 defines an energization sequence. With reference to FIGS. 62, 63, and 132, at the outset, each of the plurality of circuit segments of the surgical instrument is in sleep mode, except for the transition circuit segment 1402. The transition circuit segment 1402 is in operational mode and receives a voltage provided by the battery 1310. Consequently, all circuits of the transition circuit segment 1402 are in an energized state. In one aspect, the logic diagram 2000 defines an energization sequence that begins after the accelerometer button sensor 1405 sends a signal to the voltage control circuit 1408, as previously described. In other aspects, the energization sequence begins when another sensor such as a temperature sensor sends a signal to the voltage control circuit 1408. The temperature sensor may send the signal when a temperature of the surgical instrument sensed by the

temperature sensor exceeds a predetermined threshold.

(711) After receiving the signal, the voltage control circuit **1408** applies voltage to the processor circuit segment **1414**, causing the processor **1302** and the volatile memory **1304** to transition to operational mode. The processor **1302** transmits an energizing signal to the voltage control circuit **1408** to energize **2002** the handle circuit segment **1416**, causing the voltage control circuit **1408** to apply voltage to the handle circuit segment **1416**, causing the handle control sensors **1418** to transition to operational mode. The POST controller **1412** performs **2004** a POST to verify proper operation of the handle circuit segment **1416**. If the POST is passed successfully, the handle circuit segment **1416** remains in operational mode. The POST controller **1402** also performs **2006** a POST to verify proper operation of the battery, such as by transmitting a signal to the accelerometer button sensor **1405** to sense an incremental motor pulse generated by the motor **1432**. The incremental motor pulse indicates that the battery is properly providing voltage to the motor **1432**.

(712) The processor **1302** transmits an energizing signal to the voltage control circuit **1408** to energize **2008** the shaft circuit segment **1440**, causing the voltage control circuit **1408** to apply voltage to the shaft circuit segment **1440**, causing circuits of the shaft circuit segment **1440** to transition to operational mode. In various aspects, a detachable shaft assembly **110, 490, 510, 1110, 1210** (FIGS. **1, 25, 30, 45, 54**, respectively) comprises a memory device that stores a control program. The shaft circuit segment **1440** transmits an update signal to the processor **1302**. The update signal indicates the version of the control program stored in the memory device of the shaft assembly. When the processor **1302** receives the update signal, the processor **1302** compares **2010** the current version of the control program stored in the non-volatile memory **1308** with the version of the control program stored in the memory device of the shaft assembly. If the version is a new version, the processor **1302** updates **2012** the current version with the new version of the control program by storing the new version of the control program in the non-volatile memory **1308** and reboots **2012** the shaft assembly **110, 490, 510, 1110, 1210** or the surgical instrument **100, 480, 500, 600, 1100, 1150, 1200** (FIGS. **1-70**).

(713) To select **2014** a control program for the shaft assembly **110, 490, 510, 1110, 1210** (FIGS. **1, 25, 30, 45, 54**, respectively), the shaft module controller **1442** determines the set of shaft modules comprising the control program to be selected. The shaft module controller **1442** selects **2014** a shaft module of the set of shaft modules. The processor **1302** transmits an energizing signal to the voltage control circuit **1408** to energize **2016** the energy treatment circuit **1434**, causing the voltage control circuit **1408** to apply voltage to the energy treatment circuit **1434**, causing circuits of the energy treatment circuit **1434** to transition to operational mode. In various aspects, the detachable ultrasonic transducer **104, 104'** (FIGS. **8** and **9**, respectively) comprises the energy treatment circuit **1434** and comprises a memory device that stores a control program. The energy treatment circuit segment **1434** transmits an update signal to the processor **1302**. The update signal indicates the version of the control program stored in the memory device of the ultrasonic transducer **104, 104'**. When the processor **1302** receives the update signal, the processor **1302** compares **2018** the current version of the control program stored in the non-volatile memory **1308** with the control program version stored in the memory device of the ultrasonic transducer **104, 104'** for updating purposes.

(714) To select **2020** a control program for the ultrasonic transducer **104, 104'** (FIGS. **8** and **9**, respectively), the processor **1302** determines the energy treatment modality corresponding to the selected shaft modality. The processor **1302** executes a control program corresponding to the determined energy treatment modality. One of or a combination of the RF amplifier and safety circuit **1436** and an ultrasonic signal generator circuit **1438** implement the determined energy treatment modality. In other aspects, a transducer controller located at the ultrasonic transducer **104, 104'** may compare **2018** the control program versions and select **2020** a control program. As described above, the ultrasonic transducer and the shaft **110, 490, 510, 1110, 1210** (FIGS. **1, 25, 30, 45, 54**, respectively) implement a modality of the surgical instrument. The processor **1302** is configured to identify **2022** any mismatch between the ultrasonic transducer **104, 104'** and the shaft

assembly **110, 490, 510, 1110, 1210**. For example, the processor **1302** can detect a mismatch and transmit an energizing signal to the voltage control circuit **1408** to cause the voltage control circuit **1408** to apply voltage to the display circuit segment **1424**. The processor **1302** subsequently transmits a warning signal to the LCD display **1426** to cause the LCD display **1426** to generate **2024** a user warning. If the processor **1302** does not detect a mismatch, the processor **1302** transmits a match signal to the LCD display **1426** to cause the LCD display **1426** to generate **2026** an indication that the ultrasonic transducer **104, 104'** and the shaft assembly **110, 490, 510, 1110, 1210** match. Based on the indication of the match, a user of the surgical instrument may operate the surgical instrument.

(715) The energization sequence defined by the logic diagram **2000** of FIG. **132** differs from the deenergization sequence defined by the logic diagram **2100** of FIG. **133**. According to one aspect of the present disclosure, energizing circuits segments of the plurality of circuit segments in accordance with an energization sequence that is different from a deenergization sequence enables energy conservation through a reduction of power consumption of the surgical instrument. Specifically, energizing the segmented circuit **1401** with a different sequence from the energization sequence enables delaying or avoiding transitioning individual circuit segments with relatively high power consumption requirements to operational mode. For example, in the energization sequence defined by logic diagram **2000**, the motor circuit segment **1428** is not transitioned from sleep mode or standby mode until a user of the surgical instrument requires the motor circuit segment **1428** to be in operational mode. Non-use power drain is reduced based on this delay or avoidance in transitioning the motor circuit segment **1428** because the motor circuit segment **1428** requires relatively high power consumption in comparison to other circuit segments of the plurality of circuit segments.

(716) Moreover, in the energization sequence defined by logic diagram **2000**, the communication circuit segment **1420** and the motor circuit segment **1428** are not transitioned into an energized state. Therefore, the energization sequence defined by logic diagram **2000** differs from a deenergization sequence that comprises deenergizing each circuit segment of the plurality of circuit segments. Energy conservation is achieved based on avoiding non-use power drain of the communication circuit segment **1420** and the motor circuit segment **1428** while the other circuit segments of the plurality of circuit segments are in operational mode and a user of the surgical instrument is not using the surgical instrument. More generally, an energization sequence may be defined to conserve energy by for example, energizing circuit segments that have low power consumption requirements before energizing circuit segments that have high power consumption requirements and skipping the energization of circuit segments. If a user of the surgical instrument desires to view diagnostic information about the surgical instrument but does not require the motor of the surgical instrument in operation, an energization sequence may be defined that comprises energizing the display circuit segment **1424** and does not comprise energizing the motor circuit segment **1428**.

(717) In various aspects, the communication circuit segment **1420** and the motor circuit segment **1428** are energized into operational mode for the use of the user of the surgical instrument, after a certain time. The certain time in which the communication circuit segment **1420** and the motor circuit segment **1428** remain deenergized results in energy conservation. More generally, energization of only a subset of the plurality of circuit segments results in energy conservation, even if the remaining circuit segments are energized later.

(718) FIG. **133** is a logic diagram **2100** of a process for controlling the operation of a surgical instrument according to the energy conservation method comprising a deenergization sequence and an energization sequence, according to one aspect of the present disclosure. With reference to FIGS. **62, 63, and 133**, the logic diagram **2100** defines a deenergization sequence and an energization sequence. At the outset, each of the plurality of circuit segments of the surgical instrument is in operational mode and one or more circuit segments are performing a function. In

various aspects, a subset of the plurality of circuit segments may be in standby mode or sleep mode at the outset of performing a deenergization sequence. In the deenergization sequence defined by the logic diagram **2100**, each circuit segment of the plurality of circuit segments is transitioned from operational mode to In various aspects, the predefined standby mode transition may comprise transitioning a different subset of the plurality of circuit segments to standby mode standby mode or sleep mode. In some aspects, the deenergization sequence begins after the processor **1302** determines the surgical instrument has remained **2102** in an inactive state for a predetermined time t . An inactive state for a predetermined time t is defined by none of the plurality of circuit segments performing a function for the duration of time t . In various aspects, predetermined time t may be set based on input by a user of the surgical instrument. For example, the predefined time t may be ten seconds, thirty seconds, one minute, or some other predetermined amount of time indicated by a user through the GUI. Failure to perform a function by any individual circuit segment of the plurality of circuit segment during elapsed time t indicates an inactive state of the surgical instrument.

(719) The processor **1302** determines the correct deenergization sequence to initiate. In some aspects, the deenergization sequence to be initiated may be stored in the nonvolatile memory **1308** of the control circuit. In other aspects, the deenergization sequence to be initiated may be determined based on, for example, user initiated motions sensed by the accelerometer button sensor **1405** or other sensor, user input through the GUI, or a deenergization sequence stored in an external device that is transferred to the nonvolatile memory **1308** through an electrical connection. The processor **1302** transmits a first series of signals to the voltage control circuit **1408** according to the determined deenergization sequence. The deenergization sequence defined by the logic diagram **2100** comprises a standby mode transition sequence and a sleep mode transition sequence. The deenergization sequence may be determined based on deenergizing the circuit segments in decreasing order, starting with the circuit segment with the highest power consumption requirement to the circuit segment with the lowest power consumption requirement. The standby mode transition sequence begins when the voltage control circuit **1408** receives the series of signals, causing the voltage control circuit **1408** to reduce voltage applied to the LCD display **1426** to dim **2104** the LCD display **1426**. The dimmed LCD display **1426** is in a low power state. After a predetermined time $t_{\text{sub.1}}$, if the inactive state persists, the voltage control circuit **1408** deenergizes **2106** by reducing voltage applied to the display circuit segment **1424** to transition the display circuit segment **1424** to a low power state. After a predetermined time $t_{\text{sub.2}}$, if the inactive state persists, the voltage control circuit **1408** deenergizes **2108** by reducing voltage applied to the energy treatment circuit segment **1434** to transition the energy treatment circuit segment **1434** to a low power state.

(720) After the predetermined time $t_{\text{sub.3}}$ elapses with the surgical instrument remaining in the inactive state, the standby mode transition sequence terminates and the sleep mode transition sequence begins when the processor **1302** transmits a second series of signals to the voltage control circuit **1408** according to the determined deenergization sequence. The voltage control circuit **1408** receives the second series of signals, causing the voltage control circuit **1408** to remove voltage from circuit segments in accordance with the sleep mode transition sequence. Over the duration of a predetermined time $t_{\text{sub.4}}$, if the inactive state persists, the voltage control circuit **1408** deenergizes **2110**, **2114** by removing voltage applied to the motor circuit segment **1428** and shaft circuit segment **1440**, and deenergizes **2112** by reducing voltage applied to the handle circuit segment **1416**. The motor circuit segment **1428** and shaft circuit segment **1440** transition to a deenergized state. The handle circuit segment **1416** transitions to a low power state. The handle control sensors **1418** detect an actuation of one or more handle controls of the surgical instrument at a reduced sampling rate. Over the duration of a predetermined time $t_{\text{sub.5}}$, if the inactive state persists, the voltage control circuit **1408** deenergizes **2116**, **2118**, **2120** by removing voltage applied to the communication circuit segment **1420**, the handle circuit segment **1416**, and the processor

circuit segment **1414**. At the end of t.sub.6, the sleep mode transition sequence terminates. The transition circuit segment **1402** remains in an energized state. Energy conservation is achieved based on transitioning circuit segments with higher power consumption requirements to circuit segments with lower power consumption, in the order of descending power consumption requirements. In various aspects, if the deenergization sequence is interrupted by such as, for example, a user of the surgical instrument actuating the energy modality actuator, the processor **1302** will transmit a signal to voltage control circuit **1408** indicating which circuit segments already transitioned to a low power or a deenergized state in accordance with the interrupted deenergization sequence. Consequently, when the deenergization sequence restarts after interruption, the voltage control circuit **1408** can skip the previously completed steps of the deenergization sequence to further conserve energy.

(721) The voltage control circuit **1408** energizes **2122** by applying voltage to the processor circuit segment **1414** to transition the processor circuit segment **1414** to an energized state. The processor **1302** determines the correct energization sequence to initiate. In some aspects, the energization sequence to be initiated may be stored in the nonvolatile memory **1308** of the control circuit. In other aspects, the energization sequence to be initiated may be determined based on, for example, user initiated motions sensed by the accelerometer button sensor **1405** or other sensor, user input through the GUI, or an energization sequence stored in an external device that is transferred to the nonvolatile memory **1308** through an electrical connection. The energization sequence may be determined based on energizing the circuit segments in increasing order, starting with the circuit segment with the lowest power consumption requirement to the circuit segment with the highest power consumption requirement. The processor **1302** transmits a third series of signals to the voltage control circuit **1408** according to the determined energization sequence. The determined energization sequence begins when the voltage control circuit **1408** receives the third series of signals causing the voltage control circuit **1408** to apply voltage in accordance with the energization sequence.

(722) The voltage control circuit **1408** energizes **2124** by applying voltage to the handle circuit segment **1416** to transition the handle circuit segment **1416** to an energized state. The voltage control circuit **1408** energizes **2126** by applying voltage to the display circuit segment **1424** to transition the display circuit segment **1424** to an energized state. The voltage control circuit **1408** energizes **2128** by applying voltage to the communication circuit segment **1420** to transition the communication circuit segment **1420** to an energized state. The voltage control circuit **1408** energizes **2130** by applying voltage to the motor circuit segment **1428** to transition the motor circuit segment **1428** to an energized state. The voltage control circuit **1408** energizes **2132** by applying voltage to the energy treatment circuit segment **1434** to transition the energy treatment circuit segment **1434** to an energized state. The voltage control circuit **1408** energizes **2134** by applying voltage to the energy treatment circuit segment **1434** to transition the energy treatment circuit segment **1434** to an energized state.

(723) Energy conservation is achieved based on transitioning circuit segments with lower power consumption requirements to circuit segments with higher power consumption, in the order of ascending power consumption requirements. Therefore, even if all circuit segments of the plurality of circuit segments are transitioned to an energized state in accordance with ascending power consumption energization sequence, those circuit segments with relatively high power consumption requirements will have remained in a low power or deenergized state for a longer time in comparison to if those circuit segments transitioned according to an energization sequence that is not an ascending power consumption energization sequence. In various aspects, if the energization sequence is interrupted by for example, a user of the surgical instrument actuating the energy modality actuator, the processor **1302** will transmit a signal to voltage control circuit **1408** indicating which circuit segments already transitioned to an energized state in accordance with the interrupted energization sequence. Consequently, when the energization sequence restarts after

interruption, the voltage control circuit **1408** can skip the previously completed steps of the energization sequence to further conserve energy. As previously described, the energization sequence may comprise energizing only a subset of circuit segments of the plurality of the circuit segments. Because the remaining circuit segments of the plurality of the circuit segments were not energized, the non-use power drain of the surgical instrument is reduced. For example, in the energized sequence defined by the logic diagram **2100**, the shaft circuit segment **1440** did not transition to an energized state. Moreover, skipping a circuit segment with relatively high power consumption requirements achieves additional energy conservation. For example, the user may only need to use the LCD display **1426**. An energization sequence comprising only the display circuit segment **1424** avoid the relatively power consumption requirements of the motor circuit segment **1428** and the energy treatment circuit segment **1434**. Therefore, combining the energy conservation methods described above can achieve more energy conservation.

(724) FIG. **134** illustrates a control circuit **2200** for selecting a segmented circuit of a surgical instrument, according to an aspect of the present disclosure. With reference to FIGS. **62**, **63**, and **134**, the control circuit **2200** comprises a processor **2202**, a memory device **2204**, a multiplexer (MUX) **2206**, and an energy source **2208**. The processor **2202**, memory device **2204**, MUX **2206**, and energy source **2208** are coupled to each other and to the segmented circuit **1401** for electrical communication through one or more wired or wireless connection media. The processor **2202** may be, for example, an Analog Devices ADSP-21469 SHARC Digital Signal Processor, available from Analog Devices, Norwood, MA. The memory device **2204** may be a RAM, DRAM, SDRAM, ROM, EPROM, EEPROM, flash memory, or other suitable memory device. The MUX **2206** may be, for example, a power MUX such as the TPS2110 Power MUX, available from Texas Instruments, Dallas, TX or a plurality of suitable power MUXes. The energy source **2208** may be a battery such as the 14.4 volt nickel metal hydride (NiMH) SmartDriver Battery, available from MicroAire Surgical Instruments, Charlottesville, VA. In aspects, the voltage control circuit **1408** may comprise the control circuit **2200**. The MUX **2206** comprises a plurality of select lines S.sub.0 to S.sub.n, a plurality of inputs corresponding to circuit segments of the segmented circuit **1401**, and an output. In other aspects, the MUX **2206** may instead be a plurality of MUXes.

(725) The energy source **2208** provides voltage to the MUX **2206**. When the MUX **2206** selects an input of the plurality of inputs to be output, the circuit segment corresponding to the selected input is energized or deenergized. The control circuit **2200** comprises a plurality of electronic switches. Each individual electronic switch of the plurality of electronic switches is configured to switch between an open and closed configuration. The plurality of electronic switches may be solid state devices such as transistors or other types of switches such as wireless switches, ultrasonic switches, accelerometers, inertial sensors, among others. The electronic switch of the selected input switches to an open configuration if the control circuit **2200** is implementing a deenergization sequence comprising deenergizing the selected circuit segment. The electronic switch of the selected input switches to a closed configuration if the control circuit **2200** is implementing an energization sequence comprising energizing the selected circuit segment.

(726) FIG. **135** is a logic diagram **2300** of a process for controlling the operation of a surgical instrument according to the energy conservation method comprising a deenergization sequence and an energization sequence that is different from the deenergization sequence, according to one aspect of the present disclosure. With reference to FIGS. **62**, **63**, and **135**, the energy conservation method is performed with a surgical instrument comprising a segmented circuit **1401**, a memory device **1304**, a processor **1302**, a voltage control circuit **1408**, a safety controller **1410**, a POST controller **1412**, and an energy source **2208**. The processor **1302** is configured to control a state of each circuit segment of the plurality of circuit segments. The energy conservation method begins when the processor **1302** determines **2302** the existing state of the plurality of circuit segments. The existing state can be an energized state or a deenergized state. The processor **1302** determines **2304** whether to initiate an energization sequence or a deenergization sequence. As described previously,

an energization or deenergization sequence may be stored in the nonvolatile memory **1308** or determined based on input of a user of the surgical instrument. After determining the energization or deenergization sequence, the processor **1302** transmits **2306** a signal to the voltage control circuit **1408**. If the determined sequence is an energization sequence, the signal is an energizing signal. If the determined sequence is a deenergization sequence, the signal is a deenergizing signal. The voltage control circuit **1408** receives **2308** the transmitted signal. If the transmitted signal is an energizing signal, receiving the transmitted signal causes the voltage control circuit **1408** to apply a voltage to a circuit segment of the plurality of circuit segments. The plurality of circuit segments may comprise a transition circuit segment **1402**, a processor circuit segment **1414**, a handle circuit segment **1416**, a communication circuit segment **1420**, a display circuit segment **1424**, a motor circuit segment **1428**, an energy treatment circuit segment **1434**, and a shaft circuit segment **1440**. If the transmitted signal is a deenergizing signal, receiving the transmitted signal causes the voltage control circuit **1408** to remove a voltage from a circuit segment of the plurality of circuit segments.

(727) The voltage control circuit **1408** determines **2310** if a first circuit segment is the correct circuit segment. The correct circuit segment is determined **2310** by the voltage control circuit **1408** based on whether the circuit segment is in accordance with the energization or deenergization sequence determined by the processor **1302**. If the voltage control circuit **1408** determines **2310** that the first circuit segment is an incorrect circuit segment, the voltage control circuit **1408** switches **2312** to a second different circuit segment and determines **2310** whether the second circuit segment is the correct circuit segment. If the voltage control circuit **1408** also determines **2310** that the second circuit segment is an incorrect circuit segment, the voltage control circuit **1408** switches **2312** to a third different circuit segment. The voltage control circuit **1408** switches to each of the circuit segments of the plurality of circuit segments until the voltage control circuit **1408** determines the correct circuit segment. After the voltage control circuit **1408** determines **2310** the correct circuit segment, the voltage control circuit **1408** determines **2314** whether the received signal is an energizing signal or a deenergizing signal. If the received signal is determined **2314** to be an energizing signal, a POST controller **1412** performs **2316** a POST to verify **2318** proper operation of the correct circuit segment. If the correct circuit segment fails the POST, proper operation is not verified and a GUI of the surgical instrument may display **2320** a user warning. In aspects, the POST may comprise verifying the identity of the correct circuit segment with an encryption parameter. In other aspects, the POST may comprise verifying proper operation of the correct circuit segment with an accelerometer such as the accelerometer button sensor **1405**. In various aspects, the POST controller **1412** may initiate a locking protocol comprising disabling operation the correct circuit segment. A locked out circuit segment may function substantially similarly to a circuit segment in standby mode or sleep mode. The POST controller **1412** may also initiate a reduced performance mode of the correct circuit segment. In other aspects, a safety controller **1410** may also initiate the locking protocol or reduced performance mode, such as during operation of the surgical instrument. In aspects, one or more secondary processors of the surgical instrument may be configured to perform critical functions when the processor **1302** is determined to be in a malfunctioning state based on a POST of the processor circuit segment **1414**.

(728) If the correct circuit segment passes the POST, the voltage control circuit **1408** applies **2322** voltage to the correct circuit segment to cause the correct circuit segment to transition from the deenergized state to the energized state. If the received signal is determined **2314** to be a deenergizing signal, the voltage control circuit **1408** removes **2322** voltage from the correct circuit segment to cause the correct circuit segment to transition from the energized state to the deenergized state. In some aspects, the POST controller **1412** performs a POST on the correct circuit segment after a deenergizing signal is received. The voltage control circuit **1408** determines **2324** whether the determined sequence comprises one or more circuit segments that have not transitioned in accordance with the determined sequence. If the voltage control circuit **1408** determines **2324** that there are one or more circuit segments to transition in accordance with the

determined sequence, the logic diagram **2300** terminates **2326**. The processor **1302** transmits **2306** a signal to the voltage control circuit **1408**. If the voltage control circuit **1408** determines **2324** that there are further circuit segments to transition in accordance with the determined sequence, the voltage control circuit **1408** identifies **2328** a circuit segment of the one or more circuit segments. The voltage control circuit **1408** transmits **2330** a signal identifying a circuit segment of the one or more circuit segments. Based on the received signal, the processor **1302** transmits **2306** another signal to the voltage control circuit **1408**. Therefore, the process defined by the logic diagram **2300** restarts at the transmit **2306** signal step. The process defined by the logic diagram **2300** continues until the process terminates **2326**.

(729) In one aspect, the present disclosure provides a method of conserving energy in a surgical instrument, the surgical instrument comprising a segmented circuit comprising a plurality of independently operated circuit segments, a voltage control circuit, an energy source, a memory device, and a processor coupled to the memory device, wherein the processor is configured to control a state of a circuit segment of the plurality of circuit segments, wherein the state can be an energized state or a deenergized state, the method comprising: transmitting an energizing signal from the processor to a voltage control circuit; receiving the energizing signal by the voltage control circuit to cause the voltage control circuit to apply a voltage to a circuit segment of the plurality of circuit segments; applying the voltage to the circuit segment by the voltage control circuit to cause the circuit segment to transition from the deenergized state to the energized state in accordance with an energization sequence that is different from a deenergization sequence.

(730) The method comprises deenergizing, by the voltage control circuit, the circuit segment from the energized state to the deenergized state in accordance with the deenergization sequence. The deenergization sequence may comprise transmitting a deenergizing signal from the processor to the voltage control circuit; receiving the deenergizing signal by the voltage control circuit to cause the voltage control circuit to remove the voltage from the circuit segment; removing the voltage applied to the circuit segment, by the voltage control circuit, to cause the circuit segment to transition from the energized state to the deenergized state in accordance with the deenergization sequence that is different from the energization sequence.

(731) Applying the voltage to the circuit segment by the voltage control circuit may comprise applying the voltage to: a handle control sensor circuit, a LCD circuit, a communication circuit, a motor circuit, an energy treatment circuit and a modular power circuit. Applying the voltage to the circuit segment by the voltage control circuit may comprise applying the voltage to: the energy treatment circuit, wherein the energy treatment circuit comprises a RF control circuit and an ultrasonic signal generator the modular power circuit, wherein the modular power circuit comprises a shaft module controller, wherein the shaft module controller is coupled to a modular control actuator, an end effector sensor, and a nonvolatile memory. Prior to applying the voltage to the circuit segment in accordance with the energization sequence the method further comprises performing a safety check, by a safety controller, and performing a Power On Self Test (POST), by a POST controller, to verify proper operation of the circuit segment.

(732) The method may further comprise implementing a locking protocol, wherein the locking protocol comprises disabling operation of the circuit segment by the safety controller or the POST controller. The POST may comprise verifying proper operation of the circuit segment with an accelerometer. The POST may comprise verifying the identity of the circuit segment with an encryption parameter.

(733) In another aspect, the present disclosure provides a surgical instrument comprising: a segmented circuit comprising a plurality of independently operated circuit segments, wherein a state of a circuit segment of the plurality of circuit segments can be an energized state or a deenergized state; a memory device; a processor coupled to the memory device, wherein the processor is configured to transmit an energizing signal; a voltage control circuit, wherein the voltage control circuit is configured to receive the energizing signal to be transmitted by the

processor, the energizing signal to cause the voltage control circuit to apply a voltage to a circuit segment of the plurality of circuit segments, the voltage to be applied to cause the circuit segment to transition from the deenergized state to the energized state in accordance with an energization sequence that is different from a deenergization sequence; and an energy source to power the surgical instrument.

(734) The processor may be further configured to transmit a deenergizing signal; the voltage control circuit is further configured to receive the deenergizing signal. Deenergizing the signal to cause the voltage control circuit to remove the voltage from the circuit segment, the voltage to be removed to cause the circuit segment to transition from the energized state to the deenergized state in accordance with the deenergization sequence that is different from the energization sequence.

(735) The plurality of circuit segments may comprise a handle control sensor circuit, a LCD circuit, a communication circuit, a motor circuit, an energy treatment circuit and a modular power circuit. The energy treatment circuit comprises a RF control circuit and an ultrasonic signal generator, wherein the modular power circuit comprises a shaft module controller, wherein the shaft module controller is coupled to a modular control actuator, an end effector sensor, and a nonvolatile memory.

(736) The surgical instrument may further comprise a safety controller configured to perform a safety check; and a POST controller configured to perform a Power On Self Test (POST), the safety check and the POST to verify proper operation of the circuit segment.

(737) In another aspect, the present disclosure provides a surgical instrument comprising a segmented circuit comprising a plurality of independently operated circuit segments, wherein a state of a circuit segment of the plurality of circuit segments can be an energized state or a deenergized state; a memory device; a wake up circuit to determine an energization sequence based on an output of an accelerometer, wherein the energization sequence is different from a deenergization sequence; a processor coupled to the memory device, wherein the processor is configured to transmit an energizing signal in accordance with the energization sequence; a voltage control circuit, wherein the voltage control circuit is configured to receive the energizing signal to be transmitted by the processor, the energizing signal to cause the voltage control circuit to apply a voltage to a circuit segment of the plurality of circuit segments, the voltage to be applied to cause the circuit segment to transition from the deenergized state to the energized state in accordance with the energization sequence; and an energy source to power the surgical instrument.

(738) The plurality of circuit segments may comprise a handle control sensor circuit, a LCD circuit, a communication circuit, a motor circuit, an energy treatment circuit and a modular power circuit. The energy treatment circuit may comprise a RF control circuit and an ultrasonic signal generator, wherein the modular power circuit comprises a shaft module controller, wherein the shaft module controller is coupled to a modular control actuator, an end effector sensor, and a nonvolatile memory.

(739) The surgical instrument may further comprise a safety controller configured to perform a safety check; and a POST controller configured to perform a Power On Self Test (POST), the safety check and the POST to verify proper operation of the circuit segment. The surgical instrument may further comprise a secondary processor configured to perform a critical function when the processor is determined to be in a malfunctioning state.

Modular Battery Powered Handheld Surgical Instrument with Voltage Sag Resistant Battery Pack

(740) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with voltage sag resistant battery pack. Disclosed is a system including a battery assembly for use in a modular handheld surgical instrument, wherein the battery assembly includes a primary battery pack, a secondary battery pack, and a circuit configured to supply a first output voltage to a first load of the modular handheld surgical instrument via the primary battery pack, supply a second output voltage to a second load of the modular handheld surgical instrument via the secondary battery pack, and upon sensing a sagging voltage from the primary battery pack,

supply a supplemental voltage to the first load, via the secondary battery pack, to prevent the battery assembly from supplying an output voltage below a predetermined threshold output voltage under the first load.

(741) A battery pack, optionally disposable, that includes both primary and secondary cells or at least two different types of primary cells that can compensate within the battery pack for a voltage sag to prevent the battery pack output from sagging below a predetermined threshold under load is disclosed.

(742) According to one aspect of the present disclosure, a voltage sag resistant battery pack is disclosed for use with any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-70**. The battery assembly **400**, disposable battery assembly **410**, reusable battery assembly **420**, or battery assembly **430**, described in FIGS. **16, 17, 18, and 19** respectively above, may comprise a voltage sag resistant battery pack as described herein. In particular, the battery assembly **400**, disposable battery assembly **410**, reusable battery assembly **420**, or battery assembly **430** may comprise at least a switch mode power supply circuit (e.g., FIG. **22**) or a linear power supply circuit (e.g., FIG. **24**) to restore a sagging output voltage. Various structural aspects associated with each battery assembly **400, 410, 420, 430** have been described above. Accordingly, for conciseness and clarity of disclosure, such structural aspects of each battery assembly **400, 410, 420, 430** are incorporated herein by reference and will not be repeated here.

(743) Turning now to FIG. **36**, there is shown a circuit **710** of the surgical instrument **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-70** according to various aspects of the present disclosure. In particular, the circuit **710** comprises a power supply **712** configured to deliver an output voltage and to restore a sagging output voltage. For example, the power supply **712** may be located within a housing of the battery assembly **400, 410, 420, 430** in addition to a primary battery pack including a primary battery **715, 717**, a secondary battery pack including a secondary battery **720**, and a switch mode power supply **727**. In one aspect, the primary battery **715, 717** and the secondary battery **720** each may comprise a different chemical composition, such as, for example, Li-ion, NiMH, NiCd, and the like. In another aspect, the primary battery **715, 717** and/or the secondary battery **720** may be a rechargeable battery.

(744) In yet another aspect, the primary battery **715, 717** and the secondary battery **720** may be non-rechargeable batteries such that the primary battery pack and the secondary battery pack are disposable. As shown in FIG. **36**, the primary battery **715, 717** may be used to directly power the motor control circuits **726** and the energy circuits **732** and a separate secondary battery **720** may be used to drive the switch mode power supply **727** to power not only the motor control circuits **726** and the energy circuits **732** but also the handle electronic circuits **730**. As discussed above, the primary battery **715, 717** may comprise a number of Li-ion batteries (e.g., four) and the secondary battery **720** may comprise a number of NiMH batteries (e.g., two), for example, as shown in FIG. **17**.

(745) In this vein, FIG. **22** depicts an example switch mode power supply circuit **460** usable in power supply **712** of FIG. **36**. In particular, the switch mode power supply circuit **460** comprises a switching regulator **464** configured to produce an output voltage $V_{sub.out}$ from an input voltage $V_{sub.in}$. With reference to FIG. **36** in view of FIG. **21**, the input voltage $V_{sub.in}$ in FIG. **22** corresponds to $V_{sub.x}$ in FIG. **21** delivered by the secondary battery **454** and the output voltage $V_{sub.out}$ in FIG. **22** corresponds to $V_{sub.b}$ in FIG. **21** delivered by the switch mode power supply circuit **460**. Details of an example switching regulator **464** are depicted in FIG. **23** described above. Notably, in line with the description of FIG. **21** above, the output voltage $V_{sub.out}$ of FIG. **22** may be greater than a desired output voltage $V_{sub.o}$ of the supplemental power source circuit **450** to accommodate a voltage drop across the diode **458**. In particular, as shown in FIG. **21**, the diode **458** may be placed at the output of switch mode power supply **727** in FIG. **36** to allow current to flow only from the switch mode power supply **727** to the motor control circuits **726**, the energy circuits

732, and the handle electronic circuits 730 and to sense voltage sag at the output of the switch mode power supply 727. Ultimately, the output voltage $V_{sub.o}$ may be a voltage required by (i) the motor control circuits 726 to drive the motor 729 and/or (ii) the energy circuits 732 to drive the ultrasonic transducer 734 and/or the high-frequency (e.g., RF) current electrode 736.

(746) Again in reference to FIG. 36 in view of FIG. 21, when the switch 718, 453 (FIGS. 36, 21) is closed, the primary battery 715, 717, 452a, 452b, 452c, 452d (FIGS. 36, 21) delivers the output voltage ($V_{sub.o}$) directly to the motor control circuits 726 and the energy circuits 732. For example, the switch 718 may be closed when the primary battery pack including primary battery 715, 717 is inserted into the battery assembly 400, 410, 420, 430 (FIGS. 16-19). It should be understood that the switch 718 may be eliminated such that primary battery 715, 717 is electrically connected to the circuit 710 when the power supply 712 is attached to the surgical instrument 100, 480, 500, 600, 1100, 1150, 1200 described herein in connection with FIGS. 1-70.

(747) In a first scenario, as the primary battery 715, 717 maintains the output voltage $V_{sub.o}$ (e.g., no sagging $V_{sub.o}$, $V_{sub.o}$ required by (i) the motor control circuits 726 to drive the motor 729 and/or (ii) the energy circuits 732 to drive the ultrasonic transducer 734 and/or the high-frequency (e.g., RF) current electrode 736 is supplied) the secondary battery 720 drives the switch mode power supply 727 to power handle electronics circuits 730 (e.g., to drive control electronics) when switch 723 is closed. As described above, the switch 723 may be closed when the secondary battery pack including the secondary battery 720 is inserted into the battery assembly 400, 410, 420, 430. It should be understood that the switch 723 may be eliminated such that the secondary battery 720 is electrically connected to the circuit 710 when the power supply 712 is attached to the surgical instrument 100, 480, 500, 600, 1100, 1150, 1200 described herein in connection with FIGS. 1-70. Notably, with reference to FIG. 21, when the output voltage $V_{sub.o}$ is not sagging, the output voltage $V_{sub.o}$ is greater than the output voltage $V_{sub.b}$ from the switch mode power supply 456, and the diode 458 is off and does not conduct.

(748) In a second scenario, if/when the primary battery 715, 717 is unable to maintain the output voltage $V_{sub.o}$ (e.g., voltage sagging occurs or begins to occur, $V_{sub.o}$ required by (i) the motor control circuits 726 to drive the motor 729 and/or (ii) the energy circuits 732 to drive the ultrasonic transducer 734 and/or the high-frequency (e.g., RF) current electrode 736 is not suppliable), the secondary battery 720 drives the switch mode power supply 727 to not only deliver power to the handle electronics circuits 730 but also to deliver supplemental power to the motor control circuits 726 and/or the energy circuits 732 when switch 723 is closed. Similar to above, the switch 723 may be closed when the secondary battery pack including the secondary battery 720 is inserted into the battery assembly 400, 410, 420, 430. It should be understood that the switch 723 may be eliminated such that the secondary battery 720 is electrically connected to the circuit 710 when the power supply 712 is attached to the surgical instrument 100, 480, 500, 600, 1100, 1150, 1200 described herein in connection with FIGS. 1-70. This supplemental power enables the primary battery to maintain the output voltage $V_{sub.o}$ demanded by the motor control circuits 726 and/or the energy circuits 732 or at least a minimum $V_{sub.o}$ required by the motor control circuits 726 and/or the energy circuits 732. Notably, with reference to FIG. 21, when the output voltage $V_{sub.o}$ sags below $V_{sub.b}$ by more than the diode 458 turn-on voltage (e.g., ~0.7V), the diode 458 turns-on and conducts at which point the output $V_{sub.b}$ minus ~0.7V is applied to the output $V_{sub.o}$. This condition persists until the output voltage $V_{sub.o}$ increases above $V_{sub.b}$ to turn off the diode 458. Accordingly, as described in FIG. 21 above, the switch mode power supply 727 in FIG. 36 is capable of supplying additional current to the motor control circuits 726 and/or the energy circuits 732 when needed.

(749) In another aspect of the present disclosure, a linear power supply circuit 470 (FIG. 24) may supplant the switch mode power supply circuit 456, 460, 727 (FIGS. 21, 22, 36). In light of FIG. 36, the power supply 712 may include a battery assembly 400, 410, 420, 430 comprising a primary battery pack including a primary battery 715, 717, a secondary battery pack including a secondary

battery 720, and a linear power supply (e.g., replacing switch mode power supply 727 shown in FIG. 36). In one aspect, the primary battery 715, 717 and the secondary battery 720 each may comprise a different chemical composition (e.g., Li-ion, NiMH, NiCd, among others).

(750) In another aspect, the primary battery 715, 717 and/or the secondary battery 720 may be a rechargeable battery. In yet another aspect, the primary battery 715, 717 and the secondary battery 720 may be non-rechargeable batteries such that the primary battery pack and the secondary battery pack are disposable. Similar to the description above, the circuit 710 comprising the power supply 712 is configured to deliver an output voltage and to restore a sagging output voltage. In light of FIG. 36, the primary battery 715, 717 may be used to directly power the motor control circuits 726 and the energy circuits 732 and a separate secondary battery 720 may be used to drive the linear power supply to power not only the motor control circuits 726 and the energy circuits 732 but also the handle electronic circuits 730. For example, the primary battery 715, 717 may comprise a number of Li-ion batteries (e.g., four) and the secondary battery 720 may comprise a number of NiMH batteries or NiCd batteries (e.g., two) as shown in FIG. 17, for example. In this vein, FIG. 24 depicts an example linear power supply circuit 470 usable in the power supply 712 shown in FIG. 36. In particular, the linear power supply circuit 470 comprises a transistor 472 configured to produce an output voltage $V_{sub.out}$ from an input voltage $V_{sub.in}$.

(751) With reference to FIG. 36 in view of FIG. 21, the input voltage $V_{sub.in}$ shown in FIG. 24 corresponds to voltage $V_{sub.x}$ in FIG. 21 supplied by secondary battery 454 and the output voltage $V_{sub.out}$ shown in FIG. 24 corresponds to the voltage $V_{sub.b}$ shown in FIG. 21 supplied by the linear power supply circuit 470. Notably, in line with the description of FIG. 21 above, the output voltage $V_{sub.out}$ shown in FIG. 24 may be greater than a desired output voltage $V_{sub.o}$ to accommodate a voltage drop across the diode 458. For example, in view of FIG. 21, the diode 458 may be placed at the output of the linear power supply to allow current to only flow from the linear power supply to the motor control circuits 726, the energy circuits 732, and the handle electronic circuits 730 and to sense voltage sag at the output of the linear power supply. Ultimately, the output voltage $V_{sub.o}$ may be a voltage required by (i) the motor control circuits 726 to drive the motor 729 and/or (ii) the energy circuits 732 to drive the ultrasonic transducer 734 and/or the high-frequency (e.g., RF) current electrode 736.

(752) Again in reference to FIG. 36 in view of FIG. 21, when the switch 718, 453 (FIGS. 36, 21) is closed, the primary battery 715, 717, 452a, 452b, 452c, 452d (FIGS. 36, 21) delivers output voltage ($V_{sub.o}$) directly to the motor control circuits 726 and the energy circuits 732. For example, the switch 718 may be closed when the primary battery pack including primary battery 715, 717 is inserted into the battery assembly 400, 410, 420, 430. It should be understood that the switch 718 may be eliminated such that the primary battery 715, 717 is electrically connected to the circuit 710 when the power supply 712 is attached to the surgical instrument 100, 480, 500, 600, 1100, 1150, 1200 described herein in connection with FIGS. 1-70.

(753) In a first scenario, as the primary battery 715, 717 maintains the output voltage $V_{sub.o}$ (e.g., no sagging $V_{sub.o}$, $V_{sub.o}$ required by (i) the motor control circuits 726 to drive the motor 729 and/or (ii) the energy circuits 732 to drive the ultrasonic transducer 734 and/or the high-frequency (e.g., RF) current electrode 736 is supplied) secondary battery 720 drives the linear power supply (e.g., replacing switch mode power supply 727 shown in FIG. 36) to power the handle electronics circuits 730 (e.g., to drive control electronics), when the switch 723 is closed. As described above, the switch 723 may be closed when the secondary battery pack including secondary battery 720 is inserted into the battery assembly 400, 410, 420, 430. It should be understood that the switch 723 may be eliminated such that the secondary battery 720 is electrically connected to the circuit 710 when the power supply 712 is attached to the surgical instrument 100, 480, 500, 600, 1100, 1150, 1200 described herein in connection with FIGS. 1-70. Notably, with reference to FIG. 21, when the output voltage $V_{sub.o}$ is not sagging, the output voltage $V_{sub.o}$ is greater than the output voltage $V_{sub.b}$ from the linear power supply, and the diode 458 is off and does not conduct.

(754) In a second scenario, if/when the primary battery **715**, **717** is unable to maintain the output voltage $V_{sub.o}$ (e.g., voltage sagging occurs or begins to occur, $V_{sub.o}$ required by (i) the motor control circuits **726** to drive the motor **729** and/or (ii) the energy circuits **732** to drive the ultrasonic transducer **734** and/or the high-frequency (e.g., RF) current electrode **736** is not suppliable), the secondary battery **720** drives the linear power supply (e.g., replacing switch mode power supply **727** shown in FIG. **36**) to not only deliver power to the handle electronics circuits **730** but also deliver supplemental power to the motor control circuits **726** and/or the energy circuits **732** when switch **723** is closed. Similar to above, the switch **723** may be closed when the secondary battery pack including the secondary battery **720** is inserted into the battery assembly **400**, **410**, **420**, **430**. It should be understood that the switch **723** may be eliminated such that the secondary battery **720** is electrically connected to the circuit **710** when the power supply **712** is attached to the surgical instrument **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-70**. This supplemental power enables the primary battery to maintain the output voltage $V_{sub.o}$ demanded by the motor control circuits **726** and/or the energy circuits **732** or at least a minimum $V_{sub.o}$ required by the motor control circuits **726** and/or the energy circuits **732**. Notably, with reference to FIG. **21**, when the output voltage $V_{sub.o}$ sags below $V_{sub.b}$ by more than the diode **458** turn-on voltage (e.g., $\sim 0.7V$), the diode **458** turns-on and conducts at which point the output $V_{sub.b}$ minus $\sim 0.7V$ is applied to the output $V_{sub.o}$. This condition persists until the output voltage $V_{sub.o}$ increases above $V_{sub.b}$ to turn off the diode **458**. Accordingly, the linear power supply is capable of supplying additional current to the motor control circuits **726** and/or the energy circuits **732** when needed.

(755) Next, as previously discussed, FIG. **21** depicts a supplemental power source circuit **450** to maintain a desired output voltage (e.g., required or minimum output voltage $V_{sub.o}$) according to one aspect of the present disclosure. In accordance with another aspect of the present disclosure, the secondary battery **454** of the supplemental power source circuit **450** may comprise a rechargeable battery. In this vein, it should be appreciated that use of the secondary rechargeable battery **454** (e.g., as described in the various first and/or second scenarios above) may deplete the charge of the secondary rechargeable battery **454** from a full charge. Since a full charge of the supplemental rechargeable battery **454** is desired (e.g., to avoid voltage sagging during continued use of the surgical instrument **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-70**), the supplemental power source circuit **450** may further comprise a mechanism to recharge the secondary rechargeable battery **454**. Since, as described above, the diode **458** prevents current associated with the output voltage $V_{sub.o}$ produced by the primary batteries **452a**, **452b**, **452c**, **452d** from flowing to the secondary rechargeable battery **454** (e.g., via the switch mode power supply **456** or the linear power supply, as discussed above), the supplemental power source circuit **450** may further comprise a charger **455** to recharge the secondary rechargeable battery **454**.

(756) In particular, the primary batteries **452a**, **452b**, **452c**, **452d** may deliver the output voltage $V_{sub.o}$ not only to the motor control circuits **726** (FIG. **36**) and the energy circuits **732** (FIG. **36**) but also to the charger **455** to return a depleted secondary rechargeable battery **454** to full charge and/or to keep the secondary rechargeable battery **454** at full charge. The charger **455** may be configured to charge the secondary rechargeable battery **454** only when the motor control circuits **726** and/or the energy circuits **732** are inactive (e.g., the motor **729**, the ultrasonic transducer **734**, and/or the high-frequency (e.g., RF) current electrode **736** are not being actuated). In one alternative aspect of the present disclosure, the charger **455** may be configured to charge the secondary rechargeable battery **454** irrespective of the state (e.g., active/inactive) of the motor control circuits **726** and/or the energy circuits **732**. In one various aspect, the charger **455** may be configured to charge the secondary rechargeable battery **454** when the switch **453** (FIG. **21**) is closed (e.g., when the primary battery pack (e.g., including the primary batteries **452a**, **452b**, **452c**, **452d**) is inserted into the battery assembly **400**, **410**, **420**, **430**). Notably, the primary battery pack (e.g., including the primary batteries **452a**, **452b**, **452c**, **452d**) of the battery assembly **400**, **410**,

420, 430 may be replaceable to recharge the secondary rechargeable battery **454**. In one example, the primary batteries **452a, 452b, 452c, 452d** are disposable non-rechargeable batteries. In another example, the primary batteries **452a, 452b, 452c, 452d** are replaceable rechargeable batteries.

(757) In one aspect, the present disclosure provides a system, comprising: a battery assembly for use in a modular handheld surgical instrument, wherein the battery assembly comprises: a primary battery pack; a secondary battery pack; and a circuit configured to: supply a first output voltage to a first load of the modular handheld surgical instrument via the primary battery pack; supply a second output voltage to a second load of the modular handheld surgical instrument via the secondary battery pack; and upon sensing a sagging voltage from the primary battery pack, supply a supplemental voltage to the first load, via the secondary battery pack, to avoid supplying the first load an output voltage below the first output voltage.

(758) The first load may comprise at least one of a motor driven by a motor control circuit, an ultrasonic transducer driven by a first energy circuit, or a high-frequency current electrode driven by a second energy circuit. The second load may comprise control electronics driven by a handle electronics circuit and at least one of a motor driven by a motor control circuit, an ultrasonic transducer driven by a first energy circuit, or a high-frequency current electrode driven by a second energy circuit.

(759) The circuit may comprise a power supply circuit positioned between the secondary battery pack and the first load, wherein the power supply circuit is configured to produce a power supply output voltage from an input voltage supplied by the secondary battery pack; and a diode positioned between an output of the power supply circuit and the first load, wherein the diode is configured to sense the sagging voltage from the primary battery pack. The diode may be configured to conduct the supplemental voltage when the sagging voltage drops below the power supply output voltage by more than a turn-on voltage associated with the diode. The supplemental voltage may comprise the power supply output voltage less the diode turn-on voltage. The diode may be configured to conduct the supplemental voltage until the sagging voltage exceeds the power supply output voltage to turn off the diode.

(760) The power supply circuit may comprise a switch mode power supply circuit or a linear power supply circuit. The circuit may be configured to be resistant to radiation sterilization. The secondary battery pack may comprise a plurality of rechargeable batteries, and wherein the circuit further comprises a charger configured to charge the plurality of rechargeable batteries to a full charge. The charger may be configured to charge the plurality of rechargeable batteries when the first load is inactive.

(761) The primary battery pack may comprise a plurality of energy cells, and wherein the secondary battery pack comprises a plurality of energy cells. The plurality of energy cells of the primary battery pack may comprise a chemical composition different than the plurality of energy cells of the secondary battery pack. The plurality of energy cells of the primary battery pack and the plurality of energy cells of the secondary battery pack may be non-rechargeable such that the battery assembly is disposable.

(762) In another aspect, the present disclosure provides a voltage sag resistant battery assembly for use in a modular handheld surgical instrument, the battery assembly comprising: a first battery pack; a second battery pack; and circuitry to: supply a first output voltage to a first load via the first battery pack; supply a second output voltage to a second load via the second battery pack; and upon sensing a sagging voltage from the first battery pack, supply a supplemental voltage to the first load, via the second battery pack, to restore the sagging voltage to the first output voltage.

(763) The circuit may comprise a power supply circuit positioned between the second battery pack and the first load, wherein the power supply circuit is configured to produce a power supply output voltage from an input voltage supplied by the second battery pack; and a diode positioned between an output of the power supply circuit and the first load, wherein the diode is configured to sense the sagging voltage from the first battery pack. The second battery pack may comprise a plurality of

rechargeable batteries, and wherein the circuit further comprises a charger configured to charge the plurality of rechargeable batteries to a full charge.

(764) In another aspect, the present disclosure provides a system, comprising a modular handheld surgical instrument; and a battery assembly coupled to the modular handheld surgical instrument, wherein the battery assembly comprises: a primary battery pack including at least one energy cell; a secondary battery pack including at least one energy cell; and a circuit configured to: supply a first output voltage to a first load of the modular handheld surgical instrument via the primary battery pack; and upon sensing a sagging voltage from the primary battery pack, supply a compensating voltage to the first load, via the secondary battery pack, to prevent the battery assembly from supplying an output voltage below a predetermined threshold output voltage under the first load.

(765) The circuit may comprise a power supply circuit positioned between the secondary battery pack and the first load, wherein the power supply circuit is configured to produce a power supply output voltage from an input voltage supplied by the secondary battery pack; and a diode positioned between an output of the power supply circuit and the first load, wherein the diode is configured to sense the sagging voltage from the primary battery pack, and wherein the compensating voltage comprises the power supply output voltage less a voltage drop associated with the diode. The compensating voltage may supplement the sagging voltage to meet the predetermined threshold output voltage.

Modular Battery Powered Handheld Surgical Instrument with Multistage Generator Circuits

(766) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with multistage generator circuits. Disclosed is a surgical instrument that includes a battery assembly, a handle assembly, and a shaft assembly where the battery assembly and the shaft assembly are configured to mechanically and electrically connect to the handle assembly. The battery assembly includes a control circuit configured to generate a digital waveform. The handle assembly includes a first stage circuit configured to receive the digital waveform, convert the digital waveform into an analog waveform, and amplify the analog waveform. The shaft assembly includes a second stage circuit coupled to the first stage circuit to receive, amplify, and apply the analog waveform to a load.

(767) FIG. 136 illustrates a generator circuit 5500 partitioned into a first stage circuit 5504 and a second stage circuit 5506, according to one aspect of the present disclosure. In one aspect, the surgical instruments 100, 470, 500, 600, 700, 1100, 1150, 1200 described herein in connection with FIGS. 1-70 may comprise a generator circuit 5500 partitioned into multiple stages. For example, a surgical instruments 100, 470, 500, 600, 700, 1100, 1150, 1200 may comprises a generator circuit 5500 partitioned into at least two circuits: a first stage circuit 5504 and a second stage circuit 5506 of amplification enabling operation of RF energy only, ultrasonic energy only, and/or a combination of RF energy and ultrasonic energy. A combination modular shaft assembly 5514 may be powered by a common first stage circuit 5504 located within the handle assembly 5512 and a modular second stage circuit 5506 integral to the modular shaft assembly 5514. As previously discussed throughout this description in connection with the surgical instruments 100, 470, 500, 600, 700, 1100, 1150, 1200, the battery assembly 5510 and the shaft assembly 5514 are configured to mechanically and electrically connect to the handle assembly 5512. The end effector assembly is configured to mechanically and electrically connect the shaft assembly 5514.

(768) Turning now to FIG. 136, there is shown a generator circuit 5500 partitioned into multiple stages located in multiple modular assemblies of a surgical instrument, such as the surgical instruments 100, 470, 500, 600, 700, 1100, 1150, 1200 described herein in connection with FIGS. 1-70, for example. In one aspect, a control stage circuit 5502 may be located in a battery assembly 5510 of the surgical instrument. The control circuit 5502 is a control circuit 210 as described in connection with FIG. 14. The control circuit 210 comprises a processor 214, which includes internal memory 217 (e.g., volatile and non-volatile memory), and is electrically coupled to a

battery **211**. The battery **211** supplies power to first, second, and third stage circuits **5504**, **5506**, **5508**, respectively. As previously discussed, the control circuit **210** generates a digital waveform **1800** (FIG. **67**) using circuits and techniques described in connection with FIGS. **65** and **66**. Returning to FIG. **136**, the digital waveform **1800** may be configured to drive an ultrasonic transducer, high-frequency (e.g., RF) electrodes, or a combination thereof either independently or simultaneously. If driven simultaneously, filter circuits may be provided in the corresponding first stage circuits **5504** to select either the ultrasonic waveform or the RF waveform. Such filtering techniques are described in commonly owned U.S. patent application Ser. No. 15/265,293, titled TECHNIQUES FOR CIRCUIT TOPOLOGIES FOR COMBINED GENERATOR, now U.S. Pat. No. 10,610,286, which is herein incorporated by reference in its entirety.

(769) The first stage circuits **5504** (e.g., the first stage ultrasonic drive circuit **177**, the first stage RF drive circuit **702**, and the first stage sensor drive circuit **219**) are located in a handle assembly **5512** of the surgical instrument. As previously described, the control circuit **210** provides the ultrasonic drive signal to the first stage ultrasonic drive circuit **177** via outputs SCL-A/SDA-A of the control circuit **210**. The first stage ultrasonic drive circuit **177** is described in detail in connection with FIG. **11**. The control circuit **210** provides the RF drive signal to the first stage RF drive circuit **702** via outputs SCL-B/SDA-B of the control circuit **210**. The first stage RF drive circuit **702** is described in detail in connection with FIG. **34**. The control circuit **210** provides the sensor drive signal to the first stage sensor drive circuit **219** via outputs SCL-C/SDA-C of the control circuit **210**. Generally, each of the first stage circuits **5504** includes a digital-to-analog (DAC) converter and a first stage amplifier section to drive the second stage circuits **5506**. The outputs of the first stage circuits **5504** are provided to the inputs of the second stage circuits **5506**.

(770) The control circuit **210** is configured to detect which modules are plugged into the control circuit **210**. For example, the control circuit **210** is configured to detect whether the first stage ultrasonic drive circuit **177**, the first stage RF drive circuit **702**, or the first stage sensor drive circuit **219** located in the handle assembly **5504** is connected to the battery assembly **5502**. Likewise, each of the first stage circuits **5504** can detect which second stage circuits **5506** are connected thereto and that information is provided back to the control circuit **210** to determine the type of signal waveform to generate. Similarly, each of the second stage circuits **5506** can detect which third stage circuits **5508** or components are connected thereto and that information is provided back to the control circuit **210** to determine the type of signal waveform to generate.

(771) In one aspect, the second stage circuits **5506** (e.g., the ultrasonic drive second stage circuit **166**, the RF drive second stage circuit **574**, and the sensor drive second stage circuit **221**) are located in a shaft assembly **5514** of the surgical instrument. As previously described, the first stage ultrasonic drive circuit **177** provides a signal to the second stage ultrasonic drive circuit **166** via outputs US-Left/US-Right. The second stage ultrasonic drive circuit **166** is described in detail in connection with FIGS. **12** and **13**. In addition to a transformer (FIGS. **12** and **13**), the second stage ultrasonic drive circuit **166** also may include filter, amplifier, and signal conditioning circuits. The first stage high-frequency (RF) current drive circuit **702** provides a signal to the second stage RF drive circuit **574** via outputs RF-Left/RF-Right. The second stage RF drive circuit **574** is described in detail in connection with FIG. **35**. In addition to a transformer and blocking capacitors **706**, **708** (FIG. **35**), the second stage RF drive circuit **574** also may include filter, amplifier, and signal conditioning circuits. The first stage sensor drive circuit **219** provides a signal to the second stage sensor drive circuit **221** via outputs Sensor-1/Sensor-2. The second stage sensor drive circuit **221** may include filter, amplifier, and signal conditioning circuits depending on the type of sensor. The outputs of the second stage circuits **5506** are provided to the inputs of the third stage circuits **5508**.

(772) In one aspect, the third stage circuits **5508** (e.g., the ultrasonic transducer **130**, the RF electrodes **223a**, **223b**, and the sensors) may be located in various assemblies **5516** of the surgical instruments. In one aspect, the second stage ultrasonic drive circuit **166** provides a drive signal to the ultrasonic transducer **130** stack. In one aspect, the ultrasonic transducer **130** is located in the

ultrasonic transducer assembly of the surgical instrument. In other aspects, however, the ultrasonic transducer **130** may be located in the handle assembly **5512**, the shaft assembly **554**, or the effector. In one aspect, the second stage RF drive circuit **574** provides a drive signal to the RF electrodes **223a**, **223b**, which are generally located in the end effector portion of the surgical instrument. In one aspect, the second stage sensor drive circuit **221** provides a drive signal to various sensors **225** located throughout the surgical instrument.

(773) FIG. **137** illustrates a generator circuit **5600** partitioned into multiple stages where a first stage circuit **5604** is common to the second stage circuit **5606**, according to one aspect of the present disclosure. In one aspect, the surgical instruments **100**, **470**, **500**, **600**, **700**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-70** may comprise a generator circuit **5600** partitioned into multiple stages. For example, a surgical instruments **100**, **470**, **500**, **600**, **700**, **1100**, **1150**, **1200** may comprises a generator circuit **5600** partitioned into at least two circuits: a first stage circuit **5604** and a second stage circuit **5606** of amplification enabling operation of high-frequency (RF) energy only, ultrasonic energy only, and/or a combination of RF energy and ultrasonic energy. A combination modular shaft assembly **5614** may be powered by a common first stage circuit **5604** located within the handle assembly **5612** and a modular second stage circuit **5606** integral to the modular shaft assembly **5614**. As previously discussed throughout this description in connection with the surgical instruments **100**, **470**, **500**, **600**, **700**, **1100**, **1150**, **1200**, the battery assembly **5610** and the shaft assembly **5614** are configured to mechanically and electrically connect to the handle assembly **5612**. The end effector assembly is configured to mechanically and electrically connect the shaft assembly **5614**.

(774) As shown in the example of FIG. **137**, the battery assembly **5610** portion of the surgical instrument comprises a first control circuit **560**, which includes the control circuit **210** previously described. The handle assembly **5612**, which connects to the battery assembly **5610**, comprises a common first stage drive circuit **177**. As previously discussed, the first stage drive circuit **177** is configured to drive ultrasonic, high-frequency (RF) current, and sensor loads. The output of the common first stage drive circuit **177** can drive any one of the second stage circuits **5606** such as the second stage ultrasonic drive circuit **166**, the second stage high-frequency (RF) current drive circuit **574**, and/or the second stage sensor drive circuit **221**. The common first stage drive circuit **177** detects which second stage circuit **5606** is located in the shaft assembly **5614** when the shaft assembly **5614** is connected to the handle assembly **5612**. Upon the shaft assembly **5614** being connected to the handle assembly **5612**, the common first stage drive circuit **177** determines which one of the second stage circuits **5606** (e.g., the second stage ultrasonic drive circuit **166**, the second stage RF drive circuit **574**, and/or the second stage sensor drive circuit **221**) is located in the shaft assembly **5614**. The information is provided to the control circuit **210** located in the handle assembly **5610** in order to supply a suitable digital waveform **1800** (FIG. **67**) to the second stage circuit **5606** to drive the appropriate load, e.g., ultrasonic, RF, or sensor. It will be appreciated that identification circuits may be included in the third stage circuits **5608** such as the ultrasonic transducer **130**, the electrodes **223a**, **223b**, or the sensors **225**. Thus, when a third stage circuit **5608** is connected to a second stage circuit **5606**, the second stage circuit **5606** knows the type of load that is required based on the identification information.

(775) In one aspect, the present disclosure provides, a surgical instrument, comprising: a battery assembly, comprising a control circuit comprising a battery, a memory coupled to the battery, and a processor coupled to the memory and the battery, wherein the processor is configured to generate a digital waveform; a handle assembly comprising a first stage circuit coupled to the processor, the first stage circuit comprising a digital-to-analog (DAC) converter and a first stage amplifier circuit, wherein the DAC is configured to receive the digital waveform and convert the digital waveform into an analog waveform, wherein the first stage amplifier circuit is configured to receive and amplify the analog waveform; and a shaft assembly comprising a second stage circuit coupled to the first stage amplifier circuit to receive the analog waveform, amplify the analog waveform, and

apply the analog waveform to a load; wherein the battery assembly and the shaft assembly are configured to mechanically and electrically connect to the handle assembly.

(776) The load may comprise any one of an ultrasonic transducer, an electrode, or a sensor, or any combinations thereof. The first stage circuit may comprise a first stage ultrasonic drive circuit and a first stage high-frequency current drive circuit. The control circuit may be configured to drive the first stage ultrasonic drive circuit and the first stage high-frequency current drive circuit independently or simultaneously. The first stage ultrasonic drive circuit may be configured to couple to a second stage ultrasonic drive circuit. The second stage ultrasonic drive circuit may be configured to couple to an ultrasonic transducer. The first stage high-frequency current drive circuit may be configured to couple to a second stage high-frequency drive circuit. The second stage high-frequency drive circuit may be configured to couple to an electrode.

(777) The first stage circuit may comprise a first stage sensor drive circuit. The first stage sensor drive circuit may be configured to a second stage sensor drive circuit. The second stage sensor drive circuit may be configured to couple to a sensor.

(778) In another aspect, the present disclosure provides a surgical instrument, comprising: a battery assembly, comprising a control circuit comprising a battery, a memory coupled to the battery, and a processor coupled to the memory and the battery, wherein the processor is configured to generate a digital waveform; a handle assembly comprising a common first stage circuit coupled to the processor, the common first stage circuit comprising a digital-to-analog (DAC) converter and a common first stage amplifier circuit, wherein the DAC is configured to receive the digital waveform and convert the digital waveform into an analog waveform, wherein the common first stage amplifier circuit is configured to receive and amplify the analog waveform; and a shaft assembly comprising a second stage circuit coupled to the common first stage amplifier circuit to receive the analog waveform, amplify the analog waveform, and apply the analog waveform to a load; wherein the battery assembly and the shaft assembly are configured to mechanically and electrically connect to the handle assembly.

(779) The load may comprise any one of an ultrasonic transducer, an electrode, or a sensor, or any combinations thereof. The common first stage circuit may be configured to drive ultrasonic, high-frequency current, or sensor circuits. The common first stage drive circuit may be configured to couple to a second stage ultrasonic drive circuit, a second stage high-frequency drive circuit, or a second stage sensor drive circuit. The second stage ultrasonic drive circuit may be configured to couple to an ultrasonic transducer, the second stage high-frequency drive circuit is configured to couple to an electrode, and the second stage sensor drive circuit is configured to couple to a sensor.

(780) In another aspect, the present disclosure provides a surgical instrument, comprising a control circuit comprising a memory coupled to a processor, wherein the processor is configured to generate a digital waveform; a handle assembly comprising a common first stage circuit coupled to the processor, the common first stage circuit configured to receive the digital waveform, convert the digital waveform into an analog waveform, and amplify the analog waveform; and a shaft assembly comprising a second stage circuit coupled to the common first stage circuit to receive and amplify the analog waveform; wherein the shaft assembly is configured to mechanically and electrically connect to the handle assembly.

(781) The common first stage circuit may be configured to drive ultrasonic, high-frequency current, or sensor circuits. The common first stage drive circuit may be configured to couple to a second stage ultrasonic drive circuit, a second stage high-frequency drive circuit, or a second stage sensor drive circuit. The second stage ultrasonic drive circuit may be configured to couple to an ultrasonic transducer, the second stage high-frequency drive circuit is configured to couple to an electrode, and the second stage sensor drive circuit is configured to couple to a sensor.

Modular Battery Powered Handheld Surgical Instrument with Multiple Magnetic Position Sensors

(782) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with multiple magnetic position sensors. A system comprising a surgical

instrument is disclosed. The surgical instrument includes a handle, a shaft, a plurality of magnets, a plurality of sensors configured to determine a distance away from one or more of the plurality of magnets, and a processor communicatively coupled to the plurality of sensors. The processor is configured to determine a three dimensional change in position of the shaft by computing a three dimensional change in position of the one or more magnets, using the change in the distances determined by the one or more plurality of sensors.

(783) FIGS. **138-142** illustrate various aspects of the present disclosure that is directed to multiple magnetic position sensors disposed along the length of a shaft assembly of any one of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-70**. The magnetic position sensors disposed along the length of the shaft assembly are paired in different configurations allowing multiple sensors to detect a single magnet coupled to a shaft motion (e.g., articulation, end effector rotation, jaw member opening/closing) in order to determine a three dimensional position of the actuating component from a stationary reference plane and simultaneously diagnosing any error from external sources.

(784) Aspects of the present disclosure are presented for a system and surgical instrument configured to detect three dimensional position and change in position of various parts using a series of magnets and sensors. In some aspects, a surgical instrument includes a handle assembly, a shaft coupled to the handle assembly and an end effector coupled to a distal end of the shaft. Multiple magnets may be fixedly coupled to the shaft, while multiple sensors may also be coupled to the shaft and configured to determine a distance away from each of the multiple magnets. The shaft may be configured to move, such as rotate, translate, and/or articulate about an articulation joint. The magnets may be coupled to the shaft such that the magnets move along with how the shaft moves. However, the sensors may be coupled to the shaft such that the sensors remain in a stationary position while the shaft moves. For example, the shaft may include an exterior shaft and an interior shaft, such as a primary rotary driver, and the exterior shaft may be configured to move while the primary rotary driver does not. The magnets may be affixed to the exterior shaft and the sensors may be affixed to the primary rotary driver or a portion therein. The sensors may detect change in distances of three or more magnets as the shaft moves, for example, which may be processed by a processor to determine a change in three dimensional position of the shaft. The data of the sensors may be transmitted to a processor via a flexible circuit running on the inside of the primary rotary driver.

(785) In some aspects, a portion of the series of sensors and magnets may be configured to detect translation or other movements of the end effector. For example, the end effector may include a pair of jaws, where at least one of the jaws is configured to open and close via a clamp arm coupled to a portion of the primary rotary driver. The clamp arm may ultimately be communicatively coupled to a portion of the handle assembly configured to manipulate the end effector, such as a handle or a trigger. Pulling the trigger of the handle assembly may cause one or more of the jaws to open or close at the end effector. One or more of the magnets may be affixed to a portion of the clamp arm that moves when the clamp arm is manipulated. One or more of the sensors may be affixed to a portion of the shaft near the end effector that does not move when the clamp arm is manipulated. Thus, the sensors may be configured to detect a change in distance of these magnets as the clamp arm is manipulated, which may be processed by a processor to determine a change in movement of the jaws of the end effector. The data of the sensors may be transmitted to a processor via a flexible circuit running on the inside of the primary rotary driver.

(786) In some aspects, the system and surgical instrument may also be configured to determine an error condition of the surgical instrument using the series of magnets and sensors. For example, an error condition may occur if movement of the magnets is detected to exceed known tolerances or thresholds based on the detections of one or more of the sensors. For example, the shaft of the surgical instrument may be configured to rotate only so far, and if the sensors detect a change in position of one or more magnets that exceeds the known rotation or angle, then an error condition

may be generated. As another example, positions of multiple magnets may be monitored, and if one of the positions of the magnets is calculated to be inconsistent with calculated positions of the other magnets, an error condition may be generated.

(787) Referring to FIG. **138**, illustration **5100** shows an example system of shaft control electronics interconnecting inside a portion of a handle assembly and shaft assembly of a medical device such as any one of the surgical instruments **100**, **480**, **500**, **600**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-70**, according to various aspects. A module **5102** shows a portion of the inner workings of a handle assembly that is coupled to a module **5104** that comprises portions of a shaft assembly, according to some aspects. The module **5102** includes a flexible circuit **5106** that runs through a portion of the handle assembly and into the shaft assembly. More specifically, in some aspects, the flexible circuit **5106** runs through a primary rotary driver **5108**. The primary rotary driver **5108** is configured to drive rotation of at least a portion of the shaft assembly. While the primary rotary driver **5108** runs contiguously through a portion of the handle assembly and the proximal end of the shaft assembly, in this illustration, a portion of the primary rotary driver is not shown to reveal the flexible circuit **5106** inside.

(788) The proximal end of the flexible circuit **5106** may be coupled to an electric contact **5110**, which touches electrical contact points **5112** at the handle. A gear **5138** of the primary rotary driver **5108** may be coupled to a rotating gear **5140** in the handle assembly that is driven by the handle **5136**. The electric contact **5110** and contact points **5112** electrically couple the sensors **5126**, **5128**, **5130** to the control circuits such as control circuits **210** (FIG. **14**), **300** (FIG. **15**), **1300** (FIG. **62**), **1400** (FIG. **63**), **1500** (FIG. **64**), **1900** (FIG. **68A**), **1910** (FIG. **68B**), **1920** (FIG. **68C**), **1954** (FIG. **70**), for example.

(789) The distal end of the shaft assembly **5104** may be coupled to an end effector, which may include one or more jaws mechanically and electrically coupled at connector **5134**. The flexible circuit **5106** may be configured to transmit electrical signals to the end effector via the connector **5134**.

(790) Still referring to the shaft assembly **5104**, the primary rotary driver **5108** may be placed inside an exterior shaft **5114**, according to some aspects. The primary rotary driver **5108** may be configured to rotate the exterior shaft **5114** while the flexible circuit **5106** remains stationary. In some aspects, the shaft assembly **5104** may also include a distal piece of an exterior shaft **5116** that is coupled to the proximal exterior shaft **5114** via an articulation joint **5118**. While the primary rotary driver **5108** may run only through the end of the proximal exterior shaft **5114**, the flexible circuit **5106** may run through the distal exterior shaft **5116**, and may be configured to articulate and bend as the exterior shaft **5116** articulates about the articulation joint **5118**.

(791) In some aspects, the exterior shaft portions of the shaft assembly **5104** may include one or more magnets, such as magnets **5120**, **5122**, **5124**. These magnets may be affixed to the exterior shaft portions, and thus may move or change position as the exterior shaft portions move or change position. Meanwhile, the flexible circuit **5106** may include one or more sensors configured to measure distance away from one or more magnets, such as sensors **5126**, **5128**, **5130**. A Hall effect sensor is an example type of sensor configured to measure a distance away from one or more magnets. As shown, the shaft assembly **5104** may include sets of sensor-magnet pairs in close proximity to each other, such as the sensor **5126** being in close proximity to the magnet **5120**, the sensor **5128** being in close proximity to the magnet **5122**, and the sensor **5130** being in close proximity to the magnet **5124**. This configuration may allow the sensors to measure distances to only those magnets in close proximity.

(792) In some aspects, the shaft assembly **5104** may also include a translating shaft portion, such as the shaft portion **5132** configured to slide back and forth at the distal end of the shaft assembly **5104**. The magnet **5124** may be configured to translate or slide along with the shaft portion **5132**, while the sensor **5130** remains stationary, as it is attached to the flexible circuit **5106**.

(793) In some aspects, one or more of the sensor-magnet pairs may be configured to measure a

degree of rotation of the shaft assembly **5104**. For example, as the magnet **5120** rotates along with the exterior shaft **5114**, the change in distance away from the sensor **5126** may be measured. Based on the distance or the change in distance over time, it may be determined how much the exterior shaft **5114** has rotated.

(794) Similarly, in some aspects, one or more of the sensor-magnet pairs may be configured to measure a degree of articulation of the shaft assembly **5104**. For example, as the magnet **5122** articulates along with the distal exterior shaft portion **5116** about the articulation joint **5118**, the sensor **5128** may be configured to measure a distance to the magnet **5122**. Due to the placement of the sensor **5128** being slightly away from the center of the articulation joint **5118**, the distance away from the magnet **5122** will vary as the distal exterior shaft **5116** articulates. Based on the distance or the change in distance over time, it may be determined how the distal exterior shaft **116** is articulating about the articulation joint **5118**.

(795) Furthermore, in some aspects, one or more of the sensor-magnet pairs may be configured to measure an amount of translation of the shaft assembly **5104**. For example, as the magnet **5124** translates along with the translating portion of the shaft **5132**, the sensor **5130** may be configured to measure the distance away from the magnet **5124**. Based on the distance or change in distance over time, it may be determined how much the shaft assembly is translating away from the sensor **5130**.

(796) In some aspects, the computed positions or changes in positions according to the techniques described herein may be compared to predetermined tolerances. For example, a microprocessor and memory within the handle assembly of the medical device may have a table of distances or tolerances that reflect maximum ranges of movement by various parts of the shaft assembly. If it is computed that one or more of the magnets exceeds one of the values in this table, then an error condition may be set an alarm may be activated.

(797) In some aspects, any or all of these techniques may be included in a medical device to measure and monitor changes in position of the shaft assembly. The illustration **5100** provides merely some examples of where the magnets and sensors may be positioned, but it may be readily apparent to those of ordinary skill in the art how the magnets and the sensors may be positioned to achieve similar effects, and aspects are not so limited.

(798) Referring to FIG. **139**, illustration **5100** provides an example of a zoomed in portion of the flexible circuit **5106**, according to some aspects. As shown, the flexible circuit may comprise a series of substrate layers **5202**. The layers may be flexible enough to bend and twist. Hall effect sensors **5204** and **5206**, or other kinds of sensors configured to measure magnet strength, may be affixed to the flexible circuit **5106**, as shown.

(799) Referring to FIGS. **140A** and **140B**, in some aspects, a plurality of sensors may be used in combination to measure and monitor movements of the medical device, according to some aspects. For example, as shown in illustration **5160** of FIG. **140A**, a cross-sectional view of a portion of the shaft assembly shows the exterior shaft **5162** comprising one magnet **5164**. The interior shaft **5166** may include a flexible circuit **5174**. The flexible circuit **5174** may comprise three sensors **5168**, **5170**, and **5172**, positioned at various distances away from the magnet **5164**. The exterior shaft portion **5162** may be configured to rotate while the interior shaft **5166**, or at least a portion thereof, may be stationary.

(800) Referring to FIG. **140B**, illustration **5180** shows a rotational movement of the exterior shaft. As shown, the magnet **5164** rotates along with the exterior shaft **5162**. The angle of rotation is indicated by the arrow **5182** in relation to the centerline **5176**. Because the three sensors **5168**, **5170**, and **5172**, are positioned at varying distances away from the magnet **5164**, a trilateration calculation may be conducted using the three different distances to the magnet **5164** to determine more unambiguously a position of the magnet **5164** as it is being rotated. Based on the calculated position, a degree or angle of rotation of the exterior shaft **5162** may be determined.

(801) In general, with three or more sensors, a three-dimensional position of the magnets may be determined, assuming that the three or more sensors are positioned at uniquely different distances

away from the magnet to be measured. Therefore, the principles shown in illustrations **5100** and **5180** may be used to measure other types of changes in position, such as translation distances or articulation angles.

(802) In some aspects, instead of or in addition to multiple sensors, multiple magnets may be affixed to the moving portion of the shaft assembly, and the one or more sensors may be configured to measure the multiple distances of the multiple magnets to determine a three-dimensional position that way.

(803) Referring to FIG. **141**, illustration **5190** provides another example of how multiple sensors can be used to determine a three-dimensional position of one or more magnets, according to some aspects. In this example, the shaft assembly includes two parts about an articulation joint **5198**. Two sensors, **5192** and **5194**, are positioned along a flexible circuit **5199** on one side of the articulation joint **5198**. On the other side is a magnet **5196** that is configured to move along with that portion of the shaft assembly as it articulates about the articulation joint **5198**. The two sensors **5192** and **5194** may be sufficient to determine a unique three-dimensional position of the magnet **5196**, because the range of motion of the magnet **5196** is limited to only one plane of motion that remains on only one side of the multiple sensors. In general, number of sensors or magnets sufficient for determining unambiguous positions or changes in positions may be based on where the sensors in magnets are positioned, as well as how many degrees of freedom are available for the various parts to move.

(804) In some aspects, the sensors and/or magnets may be positioned with different configurations. Spacing of position sensors and magnets allows for higher resolution associated with location. For instance, sensors on opposite sides could sense the same magnet at different times, or different magnets would interact with sensors at different locations along travel. In addition, further resolution can be achieved through patterns of magnets. For instance, magnets can be spaced such that sensing two magnets in quick succession on one side, followed by another group on the other side signifies a different location than two in one on one side followed by a number of magnets on the other side. This may reduce the number of magnets or sensors required to achieve this effect.

(805) Referring to FIG. **142**, illustration **5200** shows a variation of a shaft assembly of a medical device that includes a seal to protect sensitive electronics, according to some aspects. In this case, the outside shaft **5202** includes at least two inner tubular structures. The rotary drive **5204** is still present and is enclosed by the outside shaft. Within that is a tube **5206** with flanges **5208**, such as a rubber tube with flanges. The flanges **5208** may be configured to pressed against the inside surface of the rotary shaft **5204** to form a seal. The seal may be airtight and watertight. The tube **5206** may then house electronics and other materials sensitive to liquid or other exposure, such as the flexible circuit **5210**.

(806) In one aspect, the present disclosure provides, a system comprising: a surgical instrument comprising: a handle assembly; a shaft coupled to the handle assembly; a plurality of magnets fixedly coupled to the shaft; a plurality of sensors coupled to the shaft and each configured to determine a distance away from one or more of the plurality of magnets; and a processor communicatively coupled to the plurality of sensors; wherein: the shaft is configured to change position relative to a stationary reference plane; one or more of the plurality of magnets are configured to change position corresponding to the changed position of the shaft; one or more of the plurality of sensors are further configured to determine a change in the distances of the one or more of the plurality of magnets relative to the one or more of the plurality of sensors as the one or more magnets change position; and the processor is configured to determine a three dimensional change in position of the shaft by computing a three dimensional change in position of the one or more magnets, using the change in the distances determined by the one or more plurality of sensors.

(807) The shaft may comprise an articulation joint, a first component and a second component of the shaft, the first and the second components coupled about the articulation joint; the second

component of the shaft is configured to articulate about the articulation joint; a first magnet of the plurality of magnets is fixedly coupled to the second component of the shaft; a first sensor of the plurality of sensors is coupled to the first component of the shaft; the first sensor is configured to measure a change in distance away from the first magnet as the second component of the shaft is articulated about the articulation joint; and the processor is configured to determine the three dimensional change in position of the articulation of the second component of the shaft using the measured change in distance of the first magnet away from the first sensor.

(808) The second magnet of the plurality of magnets may be fixedly coupled to the second component of the shaft at a position different from where the first magnet is coupled to the second component; the first sensor is further configured to measure a change in distance away from the second magnet as the second component of the shaft is articulated about the articulation joint; and the processor is further configured to determine the three dimensional change in position of the articulation of the second component of the shaft using the measured change in distance of the first magnet away from the first sensor and the measured change in distance of the second magnet away from the first sensor.

(809) The shaft may comprise an exterior shaft and an inner shaft positioned within the exterior shaft; the inner shaft is configured to rotate within the exterior shaft; a first magnet of the plurality of magnets is fixedly coupled to the exterior shaft; a first sensor of the plurality of sensors is fixedly coupled to the inner shaft; the first sensor is configured to measure a change in distance away from the first magnet as the exterior shaft is rotated relative to the inner shaft; and the processor is configured to determine a degree of rotation of the exterior shaft relative to the inner shaft using the measured change in distance of the first magnet away from the first sensor. A second magnet of the plurality of magnets may be fixedly coupled to the exterior shaft at a position different from where the first magnet is coupled to the exterior shaft; the first sensor is further configured to measure a change in distance away from the second magnet as the exterior shaft is rotated relative to the inner shaft; and the processor is further configured to determine the degree of rotation of the exterior shaft using the measured change in distance of the first magnet away from the first sensor and the measured change in distance of the second magnet away from the first sensor.

(810) The surgical instrument may further comprise an end effector coupled to a distal end of the shaft, the end effector comprising a pair of surgical jaws; the shaft comprises a clamp arm driver coupled to the pair of surgical jaws that is configured to translate proximally and distally to manipulate movement of the pair of surgical jaws; a first magnet of the plurality of magnets is fixedly coupled to the clamp arm driver; a first sensor of the plurality of sensors is coupled to a portion of the shaft that does not translate when the clamp arm driver translates; the first sensor is configured to measure a change in distance away from the first magnet as the clamp arm driver translates; and the processor is configured to determine a distance of translation of the clamp arm driver using the measured change in distance of the first magnet away from the first sensor.

(811) A second magnet of the plurality of magnets may be fixedly coupled to the clamp arm driver at a position different from where the first magnet is coupled to the exterior shaft; the first sensor is further configured to measure a change in distance away from the second magnet as the clamp arm driver translates; and the processor is further configured to determine the distance of translation of the clamp arm driver using the measured change in distance of the first magnet away from the first sensor and the measured change in distance of the second magnet away from the first sensor. The processor may be further configured to determine an error condition of the surgical instrument by measuring whether the change in the distances determined by the one or more plurality of sensors fails to satisfy at least one predetermined threshold. The surgical instrument may further comprise a flexible circuit configured to deliver an electrical connection to a distal end of the shaft and articulate about an articulation joint of the shaft. The surgical instrument may further comprise a rotary driver communicatively coupled to the handle assembly and configured to cause rotation of

at least a portion of the shaft.

(812) In another aspect, the present disclosure provides a surgical instrument, comprising a plurality of magnets; a plurality of sensors configured to determine a distance away from one or more of the plurality of magnets; and a processor communicatively coupled to the plurality of sensors, wherein the processor is configured to determine a three dimensional change in position of the surgical instrument by computing a three dimensional change in position of the one or more magnets, using the change in the distances determined by the one or more plurality of sensors.

(813) The processor may be configured to determine the three dimensional change in position of an articulation of a component of the surgical instrument using the measured change in distance of a first magnet away from a first sensor. The processor may be configured to determine a degree of rotation of an exterior component of the surgical instrument relative to an inner component of the surgical instrument using the measured change in distance of a first magnet away from a first sensor. The processor may be configured to determine a distance of translation of a component of the surgical instrument using the measured change in distance of the first magnet away from the first sensor. The processor may be further configured to determine an error condition of the surgical instrument by measuring whether the change in the distances determined by the one or more plurality of sensors fails to satisfy at least one predetermined threshold.

(814) The surgical instrument may further comprise a flexible circuit configured to deliver an electrical connection to a portion of the surgical instrument. The surgical instrument may further comprise a rotary driver and configured to rotate of at least a portion of the surgical instrument.

(815) In another aspect, the present disclosure provides a method of controlling a surgical instrument comprising a plurality of magnets, a plurality of sensors configured to determine a distance away from one or more of the plurality of magnets, and a processor communicatively coupled to the plurality of sensors, the method comprising: determining, by the processor, a three dimensional change in position of the surgical instrument by computing a three dimensional change in position of the one or more magnets, using the change in the distances determined by the one or more plurality of sensors.

(816) The method may comprise determining, by the processor, the three dimensional change in position of an articulation of a component of the surgical instrument using the measured change in distance of a first magnet away from a first sensor. The method may comprise determining, by the processor, a degree of rotation of an exterior component of the surgical instrument relative to an inner component of the surgical instrument using the measured change in distance of a first magnet away from a first sensor. The method may comprise determining, by processor, a distance of translation of a component of the surgical instrument using the measured change in distance of the first magnet away from the first sensor. The method may comprise determining, by the processor, an error condition of the surgical instrument by measuring whether the change in the distances determined by the one or more plurality of sensors fails to satisfy at least one predetermined threshold.

Modular Battery Powered Handheld Surgical Instrument Containing Elongated Multi-Layered Shaft

(817) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument containing elongated multi-layered shaft. Disclosed is a system that includes a surgical instrument that includes a handle assembly. The handle assembly includes a handle; a shaft assembly coupled to the handle assembly; and a flexible circuit. The handle assembly comprises a proximal portion of the flexible circuit and the shaft assembly comprises a distal portion of the flexible circuit; the shaft assembly further comprising: an exterior shaft positioned around the distal portion of the flexible circuit and configured to change position while a sub-portion of the distal portion of the flexible circuit remains stationary; and shaft control electronics comprising a stationary portion and a non-stationary portion, the stationary portion coupled to the distal portion of the flexible circuit and the non-stationary portion coupled to the exterior shaft; wherein the

stationary portion of the shaft control electronics is configured to measure a distance to the non-stationary portion of the shaft control electronics as the exterior shaft changes position.

(818) In one aspect, the present disclosure provides a system comprising a surgical instrument, the surgical instrument comprising: a handle assembly comprising a handle; a shaft assembly coupled to the handle assembly; and a flexible circuit, wherein the handle assembly comprises a proximal portion of the flexible circuit and the shaft assembly comprises a distal portion of the flexible circuit; the shaft assembly further comprising: an exterior shaft positioned around the distal portion of the flexible circuit and configured to change position while at least a sub-portion of the distal portion of the flexible circuit remains stationary; and shaft control electronics comprising a stationary portion and a non-stationary portion, the stationary portion coupled to the distal portion of the flexible circuit and the non-stationary portion coupled to the exterior shaft; wherein the stationary portion of the shaft control electronics is configured to measure a distance to the non-stationary portion of the shaft control electronics as the exterior shaft changes position.

(819) The processor may be coupled to the flexible circuit and configured to determine a three dimensional change in position of the exterior shaft by computing a three dimensional change in position of the non-stationary portion of the shaft control electronics, based on a change in distance between the stationary portion and the non-stationary portion.

(820) The handle assembly may comprise a first module comprising the proximal portion of the flexible circuit; and a second module comprising the handle; the first module configured to be decoupled from the second module. The first module may comprise a first set of contacts communicatively coupled to the proximal portion of the flexible circuit, and the second module comprises a second set of contacts communicatively coupled to the handle. The first set of contacts may be configured to be fixably interlocked to the second set of contacts while the first module is coupled to the second module. The handle may be configured to transmit electronic signals to the flexible circuit through the first and second set of contacts.

(821) The shaft assembly may comprise an articulation joint, a first component and a second component of the shaft assembly, the first and the second components coupled about the articulation joint; the second component of the shaft is configured to articulate about the articulation joint; the flexible circuit is configured to articulate within the articulation joint; the non-stationary portion of the shaft control electronics is fixedly coupled to the second component of the shaft; and the stationary component of the shaft control electronics is configured to measure a change in distance away from the non-stationary component as the second component of the shaft assembly is articulated about the articulation joint. The exterior shaft may be configured to rotate about the flexible circuit; and the stationary component of the shaft control electronics is configured to measure a change in distance away from the non-stationary component as the exterior shaft is rotated about the flexible circuit.

(822) The surgical instrument may further comprise an end effector coupled to a distal end of the shaft assembly, the end effector comprising a pair of surgical jaws; the shaft assembly comprises a clamp arm driver coupled to the pair of surgical jaws that is configured to translate proximally and distally to manipulate movement of the pair of surgical jaws; the non-stationary component of the shaft control electronics is fixedly coupled to the clamp arm driver; and the stationary component of the shaft control electronics is configured to measure a change in distance away from the non-stationary component as the clamp arm driver translates. The processor may be further configured to determine an error condition of the surgical instrument by measuring whether the change in the distances determined by the stationary component of the shaft control electronics fails to satisfy at least one predetermined threshold. The surgical instrument may further comprise a rotary driver communicatively coupled to the handle assembly and configured to cause rotation of at least a portion of the shaft assembly. A computer readable medium having no transitory signals comprising instructions that, when executed by a processor, cause the processor to perform the operations described above.

(823) In another aspect, the present disclosure provides, modular battery powered handheld surgical instrument with motor drive. Disclosed is a surgical instrument that includes a handle assembly; a shaft assembly and an end effector. The shaft assembly includes an exterior shaft, a first clutch positioned within the exterior shaft to drive a first function of the surgical instrument when engaged. A second clutch within the exterior shaft to drive a second function when engaged. A rotary driver is positioned within the exterior shaft and configured to rotate within the exterior shaft. The rotary driver includes a first clutch engagement mechanism to engage the first clutch and a second clutch engagement mechanism configured to engage the second clutch independent of the first clutch engagement mechanism engaging the first clutch, such that, at different times both the first clutch and the second clutch are engaged simultaneously only the first clutch is engaged only the second clutch is engaged and neither the first clutch nor the second clutch is engaged simultaneously.

(824) With reference now to FIGS. **143-146B**, in various aspects, the present disclosure provides a modular battery powered handheld surgical instrument with motor drive comprising a primary rotary drive configured to be selectably coupleable to at least two independent actuations (first, second, both, neither) and utilizing a clutch mechanism that is located entirely in the distal modular elongated tube of the shaft assembly. The motor drive may be adapted for use with any of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-70**.

(825) Aspects of the present disclosure are presented for a system and surgical instrument comprising a handle assembly and shaft assembly, with the shaft assembly including two or more distinct clutches configured to move various parts of the surgical instrument when engaged. The shaft assembly also includes an interior mechanism, such as a rotary drive, capable of selectively coupling to the clutches using independent actuation mechanisms. Each of the clutches may be engaged independently through the independent actuation mechanisms, such that the first clutch may be engaged only, the second clutch may be engaged only, both clutches may be engaged simultaneously, or neither of the clutches may be engaged at the same time. In some aspects, more clutches are included in the shaft assembly and may be engaged independently in similar manners. Example actions engaged by the clutches include engaging a clutch for articulating a portion of the shaft assembly, engaging another clutch to cause distal head rotation of the shaft assembly that includes an end effector, and engaging a third clutch to cause jaw closure and opening of the end effector.

(826) In some aspects, the clutches are comprised of a micro electrical clutching design, whereby an actuation mechanism inside the shaft assembly engages the clutch by activating an electric coil that creates a magnetic field. The clutch itself may include a ferrofluid that reacts in the presence of magnetism. Thus, when the actuation mechanism creates the magnetic field in close proximity to the clutch, the actuation mechanism attaches to the clutch via the magnetic field. Rotation of the rotary drive may then cause rotation of a component within the shaft assembly coupled to the clutch. The other clutches within the shaft assembly may be engaged in a similar manner.

(827) In some aspects, the rotary drive may be slidable within the shaft assembly, allowing for a single actuation mechanism to slide to different positions in order to engage multiple clutches at different times.

(828) In some aspects, the surgical instrument may include one or more locking mechanisms configured to maintain the actuation mechanism in its deactivated state until it may be unambiguously determine that one or more of the clutches is desired to be engaged. The locking mechanism may be biased in a locked state and may be automatically deactivated within the first few degrees of clutch drive motion to ensure that system is placed in a specific articulated or actuated state.

(829) Referring to FIG. **143**, illustration **5700** shows the inner workings of a portion of a shaft

assembly that is part of the surgical instrument, according to some aspects. This shaft assembly includes a rotary drive **5702** that may interact with three clutch systems, **5704**, **5706**, and **5708** through actuation mechanisms **5716**, **5718**, **5720**, respectively, coupled to a rotary drive **5702**. In this case, each of the actuation mechanisms include electrically conductive coils wrapped around the rotary drive **5702**. Each of the coils may receive power through electrically conductive wires, such as wires **5710**, **5712**, and **5714**, respectively. These wires may be coupled to an electrical power source.

(830) Each of the clutches may comprise a material or mechanism that can be activated to attach to or engage with the actuation mechanisms. For example, the clutch systems **5704**, **5706**, and **5708** each include a cylindrical cavity, **5722**, **5724**, and **5726**, respectively, positioned cylindrically around the rotary drive **5702**. These cylindrical cavities may be filled with a ferrofluid, such as a magnetorheological fluid. The ferrofluid may be resting in a deactivated state that is semi-viscous. When in the presence of magnetism, such as a magnetic field, the ferrofluid may activate, harden, and align with the magnetic field such that the ferrofluid attaches to the magnetic source. Thus, electricity flowing to each of the electrically conductive coils, causing a magnetic field, may be used to engage the clutch in its local proximity. Because each of the coils **5716**, **5718**, **5720**, may receive power independently, any and all combinations of clutches may be engaged at any particular time.

(831) In some aspects, the shaft assembly may include other components, such as an articulation joint **5728**, and an end effector comprising jaws **5742**, for example. Certain portions of the shaft assembly may also be configured to rotate longitudinally along with rotary drive, such as rotating distal portion **5738**. Each of these components may be activated and manipulated using the clutch systems described herein.

(832) For example, the clutch system **5704** may be configured to control movement about the actuation joint **5728**, according to some aspects. The clutch cavity **5722** that includes the ferrofluid may be coupled to a first articulation component **5734**. Towards the distal end of the articulation component **134** is a gear, that is coupled to a second gear of a second articulation component **5736**. When the clutch system **5704** is engaged, such as in the manner described above, the rotary drive **5702**, when rotated, may also cause the first articulation component **5734** to correspondingly rotate. The distal gear then causes the rotation of the second articulation component **5736** which causes articulation about the articulation joint **5728**. As shown in this example, because of the articulation joint **5728**, the rotary drive **5702** is actually broken up into two main parts, including a distal rotary drive component **5730** that is coupled to the proximal rotary drive component **5702** via a system of gears **5732** and other connectors, as shown.

(833) As another example, the clutch system **5706** may be configured to control rotation of the distal end of the shaft assembly, according to some aspects. The clutch cavity **5724** that includes the ferrofluid may be coupled to the rotatable distal portion **5738**, as shown. Thus, when the clutch system **5706** is engaged, such as in the manner described above, the rotary drive **5702**, when rotated, may cause rotatable distal portion **5738** to correspondingly rotate.

(834) As another example, the clutch system **5708** may be configured to control jaw movement of the jaws **5742** of the end effector, according to some aspects. The clutch cavity **5726** that includes the ferrofluid may be coupled to a connector **5740** via a series of angled threads, similar to threads of a screw. Thus, when the clutch system **5708** is engaged, rotation by the rotary driver **5702** causes the connector **5740** to move proximally and distally, along with some rotation. The longitudinal motion of the connector **5740** may pull or push a fulcrum of the jaws, causing them to open and close. In other cases, rotation of the rotary drive **5702** may cause the connector **5740** to only rotate, wherein some other mechanism may be designed to cause the jaws to open and close. Examples may include a rotating gear system that converts the rotation into translation movement, a pair of electrical contacts coupled to the distal end of the connector **5740** that activates jaw movement, and other mechanisms apparent to those with skill in the art.

(835) The example design in illustration **5700** shows that the different clutch systems may be engaged independently, meaning any combination of them may be engaged simultaneously, or separately, as desired by a user. This is achievable by the independent activations of the coils **5716**, **5718**, **5720**, via the independent wires **5710**, **5712**, **5714**. Therefore, the example design as shown allows for the shaft assembly to simultaneously articulate, rotate, and open and close the jaws, or any sub combination thereof, and aspects are not so limited. Similarly, additional clutch systems configured to perform or manipulate different actions of the shaft assembly may be further included, and are consistent with the teachings of this disclosure.

(836) Referring to FIGS. **144A**, **144B**, **144C**, **144D**, **144E**, and **144F** another variation for including multiple clutch systems is shown, according to some aspects. Referring to FIG. **144A**, in this case, the rotary drive **5802** includes a pair of permanent magnets **5804a**, **5804b**. In other cases, more than two permanent magnets may be used. The rotary drive **5802** is configured to slide back and forth, within the remaining exterior shaft portion of the shaft assembly. The rotary drive **5802** is also configured to rotate in the direction of the arrows, as shown. In some aspects, the rotary drive **5802** may be contained in a rotating primary shaft **5804** that does not slide back and forth within the exterior shaft. The rotating primary shaft **5804** may be configured to rotate when engaged with one or more clutches. The outer, exterior frame of the shaft assembly **5806** is configured to not move initially and includes a pair of cylindrical clutch cavities **5808**, **5810**. These cavities may again be filled with magnetorheological fluid that remains in a highly viscous state outside the presence of a magnetic field. The clutch cavities **5808**, **5810** may be positioned in close proximity to each other, such that the length of the magnets **5804a**, **5804b** may influence both ferrofluids within both cavities at the same time when the magnets are slid into a particular position.

(837) Referring to FIG. **144B**, the rotary drive **5802** has been slid into a place such that magnets **5804a**, **5804b** can influence both ferrofluids found in the clutch cavities **5808**, **5810** via their magnetic fields. That is, the rotary drive **5802** is slid into a position where the magnets **5804a**, **5804b** are roughly both in between the clutch cavities **5808**, **5810**. This may cause the ferrofluids to align and attach to the rotating primary shaft **5804**. When this occurs, rotation of the rotary drive **5802** causes rotation of the rotating primary shaft **5804**, along with rotation of the exterior frame **5806**. The rotation of the exterior frame **5806** may cause one of the actions described in FIG. **143** to occur. In general, shown herein is another example of how a rotary drive may be configured to engage one or more clutch mechanisms of the shaft assembly. Once a clutch is engaged, rotation of the rotary drive may cause an action to occur consistent with any of the methods for connecting a clutch to an action, described herein.

(838) Referring to FIG. **144C**, shown is a cross-sectional view of the shaft assembly when the rotary drive is not engaged with a clutch, according to some aspects. Here, the rotary drive **5802** is configured to move freely, independent of the exterior shaft portion **5806**. Because the rotary drive **5802** is not engaged with a clutch, only the rotary drive **5802** rotates, while the exterior shaft **5806** stays in place.

(839) Referring to FIG. **144D**, shown is a cross-sectional view of the shaft assembly when the rotary drive is engaged with a clutch, according to some aspects. Here, the shaded regions **5812** signify that a clutch is engaged by the ferrofluid being aligned and attaching to the rotary drive **5802**, due to the near proximity of the magnets. Thus, when the rotary drive **5802** is rotated, a component coupled to the clutch, such as the exterior shaft **5806** in this case, will similarly rotate, as shown.

(840) Referring to FIG. **144E**, in some aspects, the sliding design of the rotary drive with magnets may also allow for different combinations of clutch mechanisms to be engaged. For example, rather than having the rotary drive **5802** slid into a position that simultaneously engages both clutch cavities **5808**, **5810**, the rotary drive **5802** may be slid into place to engage only clutch cavity **5808**, as shown. In this position, the magnets **5804a**, **5804b** are able to only influence the ferrofluid in the clutch **5808**. Thus, assuming that the clutch **5808** is coupled to a separate action component that is

different than what the clutch **5810** is coupled to, then rotation of the rotary drive **5802** causes only the action component of the clutch **5808** to be engaged, while the action component of the clutch **5810** remains inert.

(841) Referring to FIG. **144F**, similarly, the rotary drive **5802** may be slid into a third position to allow engagement only of the second clutch **5810**. As shown, the magnets **5804a**, **5804b** are able to only influence the ferrofluid in the clutch **5810**. Thus, assuming that the clutch **5808** and the clutch **5810** have different action components or functions attached to them, then rotation of the rotary drive **5802** in this position causes only the action component of the clutch **5810** to be engaged, while the action component or function of the clutch **5808** remains inert. In general, because of the design of the shaft assembly that includes the two clutch cavities spaced near each other, and with the magnets in the rotary drive **5802** sufficiently long enough, it is possible for the rotary drive **5802** to engage both clutches simultaneously, either clutch only, or neither clutches at the same time.

(842) Referring to FIG. **145A**, in some aspects, the shaft assembly may include a locking element to help stabilize engagement of the clutches. The locking element may be biased into a locked state to hold the clutch engagement mechanism in a non-energize state but is automatically deactivated within a first few degrees of clutch drive motion. In this example, the locking element includes a set of ridges or teeth **5902** on the outer side of an interior shaft **5906**. An outer shaft may include a set of ridges or grooves **5904** to allow the teeth **5902** to rotate into place. If these teeth **5902** and grooves **5904** are out of alignment, then the shaft assembly may be considered in an unlocked state. Furthermore, the rotational alignment of the teeth **5902** may be controlled by a spring mechanism **5908**. The spring mechanism **5908** may be manually biased such that the distal end of the locking mechanism **5910** is retracted away from the distal gear **5912**. In some aspects, when the distal end of the locking mechanism **5910** does not engaged the distal gear **5912**, the clutch mechanism may be considered in an unlocked state.

(843) Referring to FIG. **145B**, shown is an example of when the locking element is in the locked state, according to some aspects. Here, the spring mechanism **5908** is relaxed or allowed to enter its naturally biased state. In its naturally biased state the spring mechanism **5908** causes the interior shaft **5906** to rotate, thereby causing the teeth **5902** to rotate and align with the grooves **5904**, as shown. This creates a notable space **5914** that shows the components are in alignment. In addition, the teeth at the distal end of the locking element **5910** is now pushed to engage with the gear **5912**. The distal end **5910** engages the distal gear **5912**, preventing it from moving so that the gears **5912** are unable to rotate.

(844) Referring to FIGS. **146A** and **146B**, shown are side views of the locking element, according to some aspects. In FIG. **146A**, the spring mechanism **5952** is naturally biased to push against the other locking mechanism components. This causes the teeth **5954** of the interior shaft to align with the grooves of the outer shaft **5956**. In contrast, a force pushing out towards the spring mechanism **5952** causes the spring mechanism **5952** to compress, and allows for a rotation of the teeth of the interior shaft **5954**. This shows that the teeth **5954** are out of alignment with the grooves **5956**, representing the locking element in an unlocked state.

(845) In one aspect, the present disclosure provides a system comprising a surgical instrument comprising: a handle assembly; a shaft assembly coupled to the handle assembly; and an end effector coupled to a distal end of the shaft assembly; the shaft assembly comprising: an exterior shaft; a first clutch positioned within the exterior shaft and configured to drive a first function of the surgical instrument when engaged; a second clutch positioned within the exterior shaft and configured to drive a second function of the surgical instrument when engaged; and a rotary driver positioned within the exterior shaft and configured to rotate within the exterior shaft, the rotary driver comprising: a first clutch engagement mechanism configured to engage the first clutch; and a second clutch engagement mechanism configured to engage the second clutch independent of the first clutch engagement mechanism engaging the first clutch, such that, at different times: both the

first clutch and the second clutch are engaged simultaneously; only the first clutch is engaged; only the second clutch is engaged; and neither the first clutch nor the second clutch is engaged simultaneously.

(846) The first clutch may comprise a cavity containing a magnetorheological fluid configured to be magnetized in the presence of an electric current. The first clutch engagement mechanism may comprise an electrical conduit configured to cause the first clutch engagement mechanism to engage the first clutch by generating an electrical current near the magnetorheological fluid that causes a magnetic attraction between the first clutch and the first clutch engagement mechanism. The second clutch may comprise a cavity containing the magnetorheological fluid configured to be magnetized in the presence of an electric current; and the second clutch engagement mechanism comprises a second electrical conduit configured to cause the second clutch engagement mechanism to engage the second clutch by generating a second electrical current that causes a magnetic attraction between the second clutch and the second clutch engagement mechanism.

(847) The first function may comprise a rotation of a distal end of the shaft assembly. The second function may comprise a closure of a pair of jaws of the end effector. The shaft assembly may further comprise an articulation joint; a proximal shaft component coupled to the handle assembly; and a distal shaft component coupled to the proximal component and configured to articulate about the articulation joint. The rotary shaft may further comprise a proximal rotary shaft component coupled to the handle assembly and a distal rotary shaft component coupled to the proximal rotary shaft component and configured to articulate about the articulation joint as the distal shaft component articulates. The distal rotary shaft component may comprise the first clutch engagement mechanism and the second clutch engagement mechanism.

(848) The proximal shaft component may comprise a third clutch positioned within the exterior shaft and configured to drive a third function of the surgical instrument when engaged; and the proximal rotary shaft component comprises a third clutch engagement mechanism configured to engage the third clutch independent of the first and second clutch engagement mechanisms engaging the first clutch and the second clutch, respectively. The third function may comprise an articulation of the shaft about the articulation joint. The surgical instrument may further comprise a locking mechanism.

(849) In another aspect, the present disclosure provides a surgical instrument comprising a handle assembly; a shaft assembly coupled to the handle assembly; and an end effector coupled to a distal end of the shaft; the shaft assembly comprising: an exterior frame; a first clutch positioned within the exterior frame and configured to drive a first function of the surgical instrument when engaged; a second clutch positioned within the exterior frame and configured to drive a second function of the surgical instrument when engaged; and a rotary driver having a portion positioned within the exterior frame and configured to rotate about a longitudinal axis and slide longitudinally within the exterior frame, the rotary driver comprising: a clutch engagement mechanism configured to: engage only the first clutch when the rotary driver is slid into the exterior frame at a first position; engage both the first and the second clutch simultaneously when the rotary driver is slid into the exterior frame at a second position; engage only the second clutch when the rotary driver is slid into the exterior frame at a third position; and engage neither the first nor the second clutch when the rotary driver is slid into the exterior frame at a fourth position.

Modular Battery Powered Handheld Surgical Instrument with Self-Diagnosing Control Switches for Reusable Handle Assembly

(850) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with self-diagnosing control switches for reusable handle assembly. Disclosed is a system and medical device that includes self diagnosing control switches. The control switch may be slidable within a slot in order to control activation of some function of the medical device. Due to natural wear and tear of movement of a control switch, the distances along the sliding slot that correspond to how much energy is used for the function may need to be adjusted over time in

order to reflect the changing physical attributes of the actuator mechanism. The self diagnosing control switches of the present disclosures may be configured to automatically adjust for these thresholds using, for example, Hall effect sensors and magnets. In addition, in some cases, the self diagnosing control switches may be capable of indicating external influences on the controls, as well as predict a time until replacement is needed.

(851) With reference now to FIGS. **147-149**, in various aspects, the present disclosure provides self diagnosing control switches within the battery powered, modular, reusable handle containing control switches capable of adjusting their thresholds for triggering an event by detecting degradation in their function/performance to compensate for its own wear. In one aspect, the self diagnosing control switches are configured to indicate predicted time to failure/replacement or when they have exceeded their adjustability range, requiring replacement. The self diagnosing control switches may be adapted for use with any of the surgical instruments **100, 480, 500, 600, 1100, 1150, 1200** described herein in connection with FIGS. **1-70**.

(852) Aspects of the present disclosure are presented for a system and surgical instrument that includes self diagnosing control switches, examples of which are shown in FIGS. **150-152**. The system and surgical instrument may be battery-powered, modular, and/or with a reusable handle assembly that may be capable of adjusting the thresholds which trigger an event, such as when to turn on or off power to a component of the surgical instrument. In addition, in some cases, the self diagnosing control switches may be capable of indicating external influences on the controls, as well as predict a time until replacement is needed.

(853) In some aspects, a self diagnosing control switch of the system or surgical instrument may include one or more sensors capable of measuring or detecting a signal strength of some kind, such as strength of a magnetic field. As an example, Hall-effect sensors may be located on a stationary component of the surgical instrument, such as on the inside of an outer frame of a handle assembly. One or more magnets may be placed on an actuator component, such as a sliding switch. The switch may be configured to deliver power to a component of the surgical instrument when slid to one side, and may be configured to turn power off to the component when slid to the other side. In some aspects, the actuator component can also include a spring biased element on either side of where he can slide, or at the center of its functional range.

(854) The slot in which the actuator mechanism slides in may offer a continuous voltage output, such that zero voltage is output when the actuator component is slid all the way on one side of the slot, and the voltage output continuously and monotonically increases to a maximum voltage output as the actuator component slides to the other side. The “on” threshold and the “off” thresholds for triggering the associated component with this switch may exist at some intermediary points along the sliding scale. However, due to natural wear and tear of movement of the switch and the electrical components connected to the actuator component, the distances along the sliding slot to represent when these thresholds occur may need to be adjusted over time in order to reflect the changing physical attributes of the actuator mechanism. The self diagnosing control switches of the present disclosures may be configured to automatically adjust for these thresholds using, for example, Hall effect sensors and magnets.

(855) In some aspects, the self diagnosing control switch may be also configured to deliver a warning signal to signify when the self adjusting mechanisms are reaching their limits. At this point, it may be a signal to replace the modular component that includes this failing self diagnosing control switch.

(856) Referring to FIG. **147**, graph **6201** shows an example plot of the amount of voltage output by a power switch in relation to its sliding distance within a slot of a self diagnosing control switch, according to some aspects. In this case, the X axis **6202** represents the voltage output of the control switch, while the Y axis **6204** represents displacement along the sliding slot of the control switch, starting from one side (e.g., the “off” position). While voltage is used in this example and the following figures, other measurements of energy may be used in the self diagnosing control

switches, and aspects are not so limited, including current, power, impedance, among others. Continuing with this example, the curve **6206** represents an amount of voltage output by the control switch at a given displacement along the slot within which the control switch slides. Phrased another way, the graph **6201** shows how much distance the control switch needs to be slid along the slot in order to deliver a desired output voltage. As shown, this displacement is not necessarily a one-to-one or linear relationship. For example, as shown, the initial sliding distance of the control switch is fairly insensitive to change in voltage, while the last parts of displacement of the control switch are relatively much more sensitive to change in voltage.

(857) In some aspects, the self diagnosing control switches may be configured to provide an alert if it is determined that outside influences may be trying to tamper with or disrupt the predicted displacement versus voltage profile **6206**. First off, a voltage may be detected that is beyond intended range of the control switch. These voltages are designated by the shaded regions **6212** and **6214**. If a voltage is ever detected within these regions, an alarm can be set off and may signal that there is either a malfunction or there is a suspected tampering. In addition, the expected displacement versus voltage profile curve **6206** may be recorded, such as stored in a memory coupled to a processor of the medical instrument. The displacement along the sliding slot may be measured and compared to the voltage output is. At any given point, if it is detected that there is a drastic change in voltage that does not match with displacement, compared to the previously recorded voltage at that same displacement, then it may also be determined that there is either a malfunction or a suspected tampering, and the alarm may also be raised.

(858) In some aspects, the control switch may be subjected to one or more thresholds that determine when an event occurs. For example, a first threshold **6208** may be in place to determine when a functional component associated with this control switch is powered on, e.g., representing an “on” threshold. In some aspects, this threshold **6208** is activated only in one direction. That is, the “on” threshold is utilized only when the control switch is being slid from the lower voltage to the higher voltage, and is not utilized when sliding the control switch from the higher voltage down to the lower voltage. Instead, in some aspects, a second threshold **6210** may be considered in these use cases. The second threshold **6210** may be used to determine when a second event occurs, such as when the functional component associated with this control switch is powered off, e.g., representing an “off” threshold. Again, the second threshold may be utilized only when the control switch is being slid from the higher voltage down to the lower voltage, and is not utilized when sliding the control switch from the lower voltage up to the higher voltage. In this way, the use of two or more thresholds may allow for a buffer zone **6212** in which no change in event occurs when the control switch is displaced into this zone. The use of such buffer zones may increase safety and prevent harmful dithering of quick oscillations between on and off states, for example. In general, other types of events may be codified with these determined thresholds, such as changing speeds or changing power levels, and other events apparent to those with skill in the art. Similarly, any number of thresholds may be utilized, and aspects are not so limited.

(859) The self diagnosing switches may be configured to adjust these thresholds to account for changing physical conditions over time of the electrical and mechanical components that make up this power, according to some aspects. Referring to FIG. **148**, graph **6220** provides an example of how the displacement vs. voltage profile of a control switch may change over time, due to natural wear and tear of the mechanical and electrical components. While the original plot **6206** is shown in solid line, the curve **6222** showed in dashed line represents an example of the amount of displacement needed to achieve a desired voltage for a control switch, due to natural wear and tear for using the control switch over time. In this example, the initial sliding of the control switch from the off position now produces a much more drastic voltage output. In addition, the middle of the curve **6222** shows that the voltage changes very little in the middle, and towards the maximum displacement, the voltage again changes more drastically.

(860) The changing attributes of the control switch over time may be a problem if the “on” and

“off” thresholds **6224**, **6226**, respectively, remain as they were according to the initial displacement versus voltage profile. This may be because the amount of voltage being output at an intended displacement of the control switch is now considerably different at the same amount of displacement along the sliding slot. Thus, the thresholds **6224**, **6226** may not accurately reflect when a functional component associated with the control switch has enough power to be turned on, and/or no longer has enough power and is to be turned off.

(861) To address this, in some aspects, a sensor may be coupled to the functional component or the self diagnosing control switch to measure voltage output. The self diagnosing control switch may include a system to measure displacement sliding along the slot, such as including one or more sensors, such as a hall effect sensor, and one or more tracking components, such as a magnet, to be included in or around the sliding slot. For example, a Hall effect sensor may be coupled to the stationary frame around the control switch, while the actuator component of the control switch may have a magnet coupled to it. The sensors may then deliver data to a processor that monitors the relationship between voltage output and displacement along the sliding slot. Over time, it may be determined that the voltage output has changed at a given point of displacement, based on the simultaneous readings from the different sensors. Specified thresholds for when an event (e.g., “on” or “off”) occurs may be adjusted to account either for the change in the displacement at a given voltage or the change in voltage at a given displacement. Thereafter, the processor may activate or deactivate the event in accordance with the new thresholds. In general, these thresholds may be continually adjusted based on automatic feedback of the self diagnosing control switch. In other cases, a user may manually activate a calibration or self diagnosing routine to cause the processor to perform this kind of maintenance and adjust the thresholds as needed.

(862) Referring to FIG. **149**, in some aspects, the self diagnosing control switch of the present disclosures may be configured to transmit an alert when it is determined that automatic adjustments to account for wear and tear are no longer possible. The graph **6230** provides two examples showing abnormal endpoints of the displacement versus voltage relationship, both signaling that the full range of intended voltage and/or displacement of the control switch is no longer possible. With original curve **6206** as a reference, the curve **6232** shown in heavy dashed line is an example of a situation where the maximum sliding displacement of the control switch still fails to reach even close to the maximum voltage output. That is, even at the maximum displacement, approximately only 4V-6V can be achieved. In this case, the self diagnosing control switch may be configured to transmit an alert or alarm signifying that the desired voltage cannot be achieved, or more generally, that there is a malfunction. In general, this signal may represent that repairs are needed, or that this modular component associated with this control switch needs to be replaced.

(863) As another example, the curve **6234** shown in light dashed line shows a situation where maximum sliding displacement of the control switch is unnecessary, as maximum voltage may already be achieved after just a small amount of sliding. This may also be a problem because it may signal that a mechanism for controlling the output voltage is malfunctioning. Also in this case, the self diagnosing control switch may be configured to transmit an alert or alarm signifying that proper voltage control is not present or malfunctioning. In general, this signal may represent that repairs are needed, or that this modular component associated with this control switch needs to be replaced. In general, these examples show how the self diagnosing control switch of the present disclosures may be used to provide alerts for end-of-life stages of the control switches.

(864) In addition, in some aspects, the self diagnosing control switches also may be configured to anticipate end-of-life scenarios. For example, the displacement versus voltage curves may be continually recorded over time, such that the changes over time may be monitored. These changes over time may be used to create an extrapolation profile that projects when these changes, assuming they continue at the observed rate (or based on other projected factors), will result in an abnormal endpoint, similar to the example curves **6232**, **6234**. The self diagnosing control switch may then be configured to report this projected end-of-life term, or deliver a signal representing

that there is a set amount of time—or number of uses—estimated until repairs are needed.

(865) Examples of self diagnosing control switches provided on battery powered modular surgical instrument are shown in FIGS. **150-152**. The diagnostic techniques described in connection with FIGS. **147-149** may be adapted for use with the battery powered modular surgical instruments **6301, 6502, 6602** shown in FIGS. **150-152**. Turning first to FIG. **150**, there is shown a side elevational view of one aspect of a handle assembly **6301** of a modular surgical instrument, according to one aspect of the present disclosure. The handle assembly **6301** may be engaged with an interchangeable shaft assembly (not shown). The handle assembly **6301** includes a closure trigger **6303**, pistol grip portion **6305**, an interface **6307**, and a user display **6310**, which may also be configured to receive an input from a user. The handle assembly **6301** also includes a closure release button assembly **6312**, which can be depressed by the operator to release a closure lock thereby returning an end effector (not shown) to a desired configuration. The handle assembly **6301** is shown with a socket **6314** for a battery and the battery pack is removed.

(866) The interface **6307** may comprise at least one user-actuated input device, such as a switch, that may be configured to provide functionality as described herein. According to aspects the interface **6307** may be utilized to implement an articulation function of an interchangeable shaft assembly. Additionally, according to the aspect shown in FIG. **150**, the interface **6307** comprises a plurality of user-actuated input devices, switches **6316, 6318, 6320**, which can be utilized by the operator, in part, to activate and control functions associated with an end effector of an interchangeable shaft assembly, as described herein. According to an aspect, the handle assembly **6301** may be combined with an interchangeable shaft assembly having a cutting member as described herein. In such an aspect, the switches **6316, 6318, 6320** may be used to control activation and speed of the cutting member.

(867) As shown in FIG. **150**, the switch **6316** is a button style switch and switches **6318** and **6320** are part of a toggle style switch. The interface **6307** may be configured such that the switch **6316** is dedicated to activation and/or selection of the speed of a cutting member. Further, switch **6318** may be dedicated to increasing the speed of the cutting member and the switch **6320** may be dedicated to decreasing the speed of the cutting member. Other means for controlling the switches **6318, 6320** and/or replacing functionality of the switches **6318, 6320** with a single switch device are also contemplated within the scope of the present disclosure.

(868) FIG. **151** is a side elevational view of another aspect of a handle assembly **6502** of a battery powered modular surgical instrument, according to one aspect of the present disclosure. According to aspects and with reference to FIG. **150**, the switches **6318, 6320** of the handle assembly **6301** may be replaced by a single user-actuated input device. As shown in FIG. **151**, the interface **6508** of the handle assembly **6502** comprises a rotary potentiometer **6504** that may be used to adjust the speed of cutting member. For example, in one aspect, counter-clockwise rotation of the rotary potentiometer **6504** increases the speed of the cutting member whereas clockwise rotation of the rotary potentiometer **6504** decreases the speed of the cutting member. The output of the rotary potentiometer **6504** can be provided to an external A/D converter or to an A/D converter of a controller. In other aspects, the rotary potentiometer **6504** may be replaced with a rotary encoder whose output can be provided to the controller **6402**.

(869) FIG. **152** is a side elevational view of another aspect of a handle assembly **6602** of a battery powered modular surgical instrument, according to one aspect of the present disclosure. In addition, in the aspect shown in FIG. **152**, the interface **6608** of the handle assembly **6602** comprises a slide potentiometer **6604** that may be used to adjust the speed of cutting member such that sliding the sliding bar to the left increases the speed of the cutting member whereas sliding the sliding bar to the right decreases the speed of the cutting member. The output of the slide potentiometer **6604** can be provided to an external A/D converter or to an internal A/D converter of a controller. In other aspects, the slide potentiometer **6604** may be replaced with a slide encoder whose output can be provided to the controller **6402**.

(870) According to aspects and with reference to FIGS. 151 and 152, the rotary potentiometer 6504 or the slide potentiometer 6604 may be used to replace the functionality associated with electrical contact switches. Further, referring to FIGS. 151 and 152, circuits associated with the rotary potentiometer 6504 or the slide potentiometer 6504 may be combined into a single circuit. In one aspect, the rotary potentiometer 6504 or slide potentiometer 6604 may comprise a variable resistor coupled to an A/D converter. Accordingly, a controller may receive a digitized signal from either the rotary potentiometer 6504 or slide potentiometer 6604 and provide it to a motor controller 6420 for controlling the speed of a motor.

(871) In another aspect, the present disclosure provides a system comprising: a surgical instrument comprising: a handle assembly; a shaft assembly coupled to the handle assembly; and an end effector coupled to a distal end of the shaft assembly; a self-diagnosing control switch system comprising: a control switch slidable within a slot comprising a first end and a second end of the slot, the control switch configured to: slide within the slot between the first end and the second end; and allow an amount of energy to be delivered to a functional component of the surgical instrument, the amount of energy in proportion to a degree of displacement of the control switch away from the first end of the slot; a displacement sensor configured to measure the degree of displacement of the control switch away from the first end of the slot; an energy sensor configured to measure the amount of energy delivered to the functional component; and a processor configured to: determine a threshold level of displacement of the control switch away from the first end of the slot that triggers a functional event of the functional component, based on the measured degree of displacement and the measured amount of energy delivered to the functional component.

(872) The processor may be further configured to determine a limit to the degree of displacement. The processor may be further configured to: determine that the measured degree of displacement exceeds the determined limit; and transmit an alarm based on the determined exceeded limit. The processor may be further configured to determine a limit to the amount of energy delivered to the functional component. The processor may be further configured to: determine that the measured amount of energy exceeds the determined limit; and transmit an alarm based on the determined exceeded limit. The processor may be further configured to: record, in a memory, the threshold level of displacement of the control switch as a baseline threshold level of displacement away from the first end of the slot that triggers a functional event; receive, from the energy sensor, a second measurement of an amount of energy delivered to the functional component when the control switch is positioned at the baseline threshold level of displacement; and compare the second measurement of energy to the measurement of energy used to create the baseline threshold level of displacement.

(873) The processor may be further configured to determine that the comparison of the second measurement of energy to the measurement of energy used to create the baseline threshold level of displacement satisfies a predetermined level of change; and determine an adjusted threshold level of displacement of the control switch away from the first end of the slot that triggers the functional event of the functional component, based on the comparison between the second measurement of energy and the measurement of energy used to create the baseline threshold of displacement. The processor may be further configured to calculate an end-of-life term of the control switch at which time the control switch is predicted to no longer function, based on an extrapolation calculation using the adjusted threshold level and the baseline threshold level. The displacement sensor may comprise a Hall effect sensor positioned next to the control switch, and the control switch comprises a magnet.

(874) In another aspect, the present disclosure provides a method for self-diagnosing operation of a control switch in a surgical instrument system, the method comprising: receiving, from a displacement sensor, a baseline degree of displacement of the control switch in a slidable slot of the surgical instrument system; receiving, from an energy sensor, an amount of energy to be delivered to a functional component of the surgical instrument in proportion to the measured baseline degree

of displacement of the control switch; determining a baseline threshold level of displacement of the control switch away from the first end of the slot that triggers a functional event of the functional component, based on the measured baseline degree of displacement and the measured amount of energy delivered to the functional component; recording, in a memory, the baseline threshold level of displacement of the control switch; receiving, from the energy sensor, a second measurement of an amount of energy delivered to the functional component when the control switch is positioned at the baseline threshold level of displacement; and comparing the second measurement of energy to the measurement of energy used to create the baseline threshold level of displacement.

(875) The method may further comprise determining that the comparison of the second measurement of energy to the measurement of energy used to create the baseline threshold level of displacement satisfies a predetermined level of change; and determining an adjusted threshold level of displacement of the control switch away from the first end of the slot that triggers the functional event of the functional component, based on the comparison between the second measurement of energy and the measurement of energy used to create the baseline threshold of displacement.

Modular Battery Powered Handheld Surgical Instrument with Reusable Asymmetric Handle Housing

(876) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with reusable asymmetric handle housing. Disclosed is a surgical instrument that includes a handle assembly that includes a handle housing. The handle housing comprises two asymmetric portions, a first portion configured to support mechanical and electrical components of the surgical instrument and a second portion comprising a removable cover.

(877) FIGS. **70** and **155A-155B** illustrate various configurations of reusable and serviceable handle housings for housing assemblies which are divided into two asymmetric halves such that the control circuits, wiring harness, coupling mechanisms can be supportably housed in one side of the handle housing and support all the actuation forces within that side while the other side is removably attached to cover the primary housing. The handle assemblies illustrated in FIGS. **70** and **155A-155B** can be used in the surgical instruments **100**, **470**, **500**, **600**, **700**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-69**.

(878) FIG. **153A** illustrates a cross sectional view of a reusable and serviceable handle assembly **600** with a removable service cover **6004** in an open position, according to one aspect of the present disclosure. FIG. **153B** illustrates a cross sectional view of the reusable and serviceable handle assembly **6000** with the service cover in a closed position, according to one aspect of the present disclosure. The handle assembly **600** comprises a housing **6002** and a perimeter elastomeric seal **6008** to prevent fluid from passing from inside to the outside of the handle assembly **6000**. The seal **6008** is disposed between the removable service cover **6004** and the housing **6002**. A removable switch **6006** is located and supported within the housing **6002**. The removable switch **6006** is accessible for service or replacement by removing the removable service cover **6004**. The removable switch **6006** is electrically coupled to a removable electrical contact **6010**, which is ultimately electrically coupled to a control circuit such as the control circuit **210** (FIG. **14**), **1300** (FIG. **62**), **1400** (FIG. **63**), **1500** (FIG. **64**) via interface circuits such as circuits **6550**, **6570** (FIGS. **90-91**), for example.

(879) FIG. **154A** illustrates a cross sectional view of a reusable and serviceable handle assembly **6100** with a removable service cover **6104** in an open position, according to one aspect of the present disclosure. FIG. **154B** illustrates a cross sectional view of the reusable and serviceable handle assembly **6100** with the removable service cover **6104** in a closed position, according to one aspect of the present disclosure. The handle assembly **6100** comprises a housing **6102** and a perimeter elastomeric seal **6108** to prevent fluid from passing from inside to the outside of the handle assembly **6100**. The seal **6108** is disposed between the removable service cover **6104** and the housing **6102**. The removable service cover comprises a post **6114** defining a recess **6118** to receive a first magnet **6112a**. The housing **6102** defines an aperture **6116** to receive the post **6114**.

The housing **6102** includes a second magnet **6112b** that is aligned to magnetically couple to the first magnet **6112a** when the service cover **6104** is closed as shown in FIG. **154B** when the removable service cover **6104** is magnetically attached to the housing **6102**.

(880) In one aspect, the magnets **6112a**, **6112b** can be rare-earth magnets or other strong permanent magnets made from alloys of rare-earth elements (elements in the lanthanide series, plus scandium and yttrium). Rare-earth magnets are the strongest type of permanent magnets made, producing significantly stronger magnetic fields than other types such as ferrite or alnico magnets. The magnetic field typically produced by rare-earth magnets can exceed 1.4 tesla, whereas ferrite or ceramic magnets typically exhibit fields of 0.5 to 1 tesla, for example. Two types of rare-earth magnets that may be employed, among others, are neodymium magnets and samarium-cobalt magnets. Magnetostrictive rare-earth magnets such as Terfenol-D also may be employed. Rare-earth magnets may be plated or coated to protect them from breaking, chipping, or crumbling into powder. Magnets made of alloys of yttrium and cobalt, YCo5, that have a large magnetic anisotropy constant also may be employed.

(881) TABLE 2 below provides a comparison of various types of materials for permanent magnets. Relevant properties used to compare permanent magnets are: remanence (Br), which measures the strength of the magnetic field; coercivity (Hci), the material's resistance to becoming demagnetized; energy product (BHmax), the density of magnetic energy; and Curie temperature (Tc), the temperature at which the material loses its magnetism. Rare earth magnets have higher remanence, much higher coercivity and energy product, but (for neodymium) lower Curie temperature than other types. The TABLE 2 below compares the magnetic performance of the two types of rare-earth magnet, neodymium (Nd2Fe14B) and samarium-cobalt (SmCo5), with other types of permanent magnets.

(882) TABLE-US-00002 TABLE 2 (BH).sub.max Magnet B.sub.r (T) H.sub.ci (kA/m) (kJ/m.sup.3) T.sub.c (° C.) Nd.sub.2Fe.sub.14B (sintered) 1.0-1.4 750-2000 200-440 310-400 Nd.sub.2Fe.sub.14B (bonded) 0.6-0.7 600-1200 60-100 310-400 SmCo.sub.5 (sintered) 0.8-1.1 600-2000 120-200 720 Sm(Co, Fe, Cu, Zr) 0.9-1.15 450-1300 150-240 800 (sintered) Alnico (sintered) 0.6-1.4 275 10-88 700-860 Sr-ferrite (sintered) 0.2-0.4 100-300 10-40 450

(883) With reference now to FIGS. **70** and **154A-154B**, the handle assemblies **1970**, **6000**, **6100** can be used with modular battery powered handheld surgical instruments **100**, **470**, **500**, **600**, **700**, **1100**, **1150**, **1200** described herein in connection with FIGS. **1-69** comprising modular disposable shafts, control and wiring harnesses. In one aspect, each of the handle assemblies **1970**, **6000**, **6100** is configured to asymmetrically part when opened so that the switches **1980**, **6006**, wiring harnesses, and/or control electronics can be supportably housed in one side with the other side and removably attached to cover the housing **1974**, **6002**, **6102**. In the examples illustrated in FIGS. **70** and **154A-154B**, the handle housing **1974**, **6002**, **6102** is asymmetric with sides which allow for the nesting of life limited components like the switches **1980**, **6006** motor control board, and inner electrical connectors. The housing **1974**, **6002**, **6102** includes a small slot at the top, bottom or side of the handles. A flat bladed tool can be used to apply side load to the handle assemblies **1970**, **6000**, **6100**, creating a shear load against the fasteners. As shown in FIGS. **153A-153B**, in one aspect, the fasteners holding the service cover **6104** are magnets **6112a**, **6112b**. Accordingly, the flat blade tool needs only to overcome the magnetic attraction to remove the service cover **6104** from the housing **6102**. Once the magnets **6112a**, **6112b** are moved relative to one another, the service cover **6104** easily separates from the housing **6102**. The housing **6102** also can include a rotary control that includes a mechanism to push the service cover **6104** apart from the housing **6102** in a shear mode. The magnets **6112a**, **6112b** do not easily prevent the relative movement of the service cover **6104** and the housing **6102** in this mode and one of the magnets **6112a**, **6112b** is moved apart from one another, they are easily separated.

(884) The removable switches **1980**, **6006** controls, wiring harnesses, and control boards are housed within a structural skeletal frame of the housing **1974**, **6002**, **6102**. The outer service covers

1972, 6002, 6102 are removable on one or both sides of the handle assemblies **1970, 6000, 6100** to allow servicing, maintenance, and cleaning but the skeleton protects and restrains the electronic components not the removable service covers **1972, 6002, 6102**. In one aspect, the service covers **1972, 6002, 6102** include interlocking features between them and the central skeletal system. In one aspect, as illustrated in FIGS. **153A-153B**, the magnets **6112a, 6112b** hold the removable service cover **6104** in place but the key interlocks prevent shearing forces applied to the service cover **6104** from inadvertently dislodging the service cover **6104**.

(885) FIGS. **155A-155B** illustrates one aspect of a handle assembly **6120**, according to one aspect of the present disclosure. FIG. **155A** illustrates the handle assembly **6120** in a secured fastened configuration and FIG. **155B** illustrates the handle assembly **6120** in an unlatched configuration. The handle assembly **6120** comprises a first housing **6122a** (e.g., shroud) and a second housing **6122b** (e.g., shroud) that can be latched and unlatched. A rotation knob **6124** is located on a distal end of the housing assembly **6120**. As previously discussed, the rotation knob **6124** is operably coupled to a shaft assembly (not shown). The handle assembly **6120** comprises a removable trigger **6126** that is operably coupled to an end effector (not shown). High-frequency (e.g., RF) energy and ultrasonic energy is activated using removable switches **6128a, 6128b**. The removable switches **6128a, 6128b** may be referred to as buttons, for example. An aperture **6130** is defined by the handle assembly **6120** to receive an ultrasonic transducer assembly (not shown).

(886) In the configuration shown in FIG. **155A**, the two housings **6122a, 6122b** (shrouds) of the handle assembly **6120** are secured fastened using hooked tabs **6132a, 6132b** on the first shroud **6122a**, as shown in FIG. **155B**, that snap into access slots **6134a, 6134b** defined by the second shroud **6134b**. The access slots **6134a, 6134b** enable access to the hooked tabs **6132a, 6132b**. The hooked tabs **6132a, 6132b** can be accessed at the parting line **6136** by inserting a tool to deflect the hooked tabs **6132a, 6132b** unlatching the shroud **6122a, 6122b** halves.

(887) In another aspect, the present disclosure provides a surgical instrument comprising: a handle assembly comprising a handle housing, wherein the handle housing comprises two asymmetric portions, a first portion configured to support mechanical and electrical components of the surgical instrument and a second portion comprising a removable cover.

(888) The first portion and the removable cover each may comprise a fastener to removably connect the removable cover to the first portion of the handle housing. The fastener may comprise a permanent magnet. The fastener may comprise a hooked tab and a corresponding slot to receive the hooked tab and snap fit the removable cover to the first portion of the handle housing.

(889) The surgical instrument may further comprise an elastomeric seal positioned about a perimeter of the first portion of the handle housing to provide a seal between the first portion of the handle housing and the removable cover. The surgical instrument may further comprise a removable switch is located within and supported by the first portion of the handle housing. The surgical instrument may further comprise a removable electrical contact located within and supported by the first portion of the handle housing. The surgical instrument may further comprise a removable motor located within and supported by the first portion of the handle housing. The surgical instrument may further comprise a removable trigger located within and supported by the first portion of the handle housing. The surgical instrument may further comprise a removable electrical contact located within and supported by the first portion of the handle housing. The first portion of the handle housing may define an aperture to receive a removable ultrasonic transducer assembly.

(890) In another aspect, the present disclosure provides a surgical instrument comprising: a handle assembly comprising a handle housing, wherein the handle housing comprises two asymmetric portions, a first portion configured to support mechanical and electrical components of the surgical instrument and a second portion comprising a removable cover; an elastomeric seal positioned about a perimeter of the first portion of the handle housing to provide a seal between the first portion of the handle housing and the removable cover; a removable switch is located within and

supported by the first portion of the handle housing; a removable electrical contact located within and supported by the first portion of the handle housing; a removable trigger located within and supported by the first portion of the handle housing; and a removable electrical contact located within and supported by the first portion of the handle housing.

(891) The first portion of the handle housing may define an aperture to receive a removable ultrasonic transducer assembly. The first portion and the removable cover each may comprise a fastener to removably connect the removable cover to the first portion of the handle housing. The fastener may comprise a permanent magnet. The fastener may comprise a hooked tab and a corresponding slot to receive the hooked tab and snap fit the removable cover to the first portion of the handle housing. The surgical instrument may further comprise a removable motor located within and supported by the first portion of the handle housing.

(892) In another aspect, the present disclosure provides a handle assembly, comprising a handle housing, wherein the handle housing comprises two asymmetric portions, a first portion configured to support mechanical and electrical components of the surgical instrument and a second portion comprising a removable cover, wherein the first portion and the removable cover each comprises a fastener to removably connect the removable cover to the first portion of the handle housing; an elastomeric seal positioned about a perimeter of the first portion of the handle housing to provide a seal between the first portion of the handle housing and the removable cover; a removable switch is located within and supported by the first portion of the handle housing; a removable electrical contact located within and supported by the first portion of the handle housing; a removable trigger located within and supported by the first portion of the handle housing; a removable electrical contact located within and supported by the first portion of the handle housing; and a removable motor located within and supported by the first portion of the handle housing. The fastener may comprise a permanent magnet. The fastener may comprise a hooked tab and a corresponding slot to receive the hooked tab and snap fit the removable cover to the first portion of the handle housing.

Modular Battery Powered Handheld Surgical Instrument with Curved End Effectors Having Asymmetric Engagement Between Jaw and Blade

(893) In another aspect, the present disclosure provides a modular battery powered handheld surgical instrument with curved end effectors having asymmetric engagement between jaw and blade. Disclosed is an end effector for a surgical instrument that includes an ultrasonic blade and a jaw member including an asymmetric electrode comprising a first electrode and a second electrode. The first electrode defines a first width and the second electrode defines a second width. The first width is not equal to the second width. A first gap is defined between the first electrode and the ultrasonic blade and a second gap is defined between the second electrode and the ultrasonic blade. The first gap is not equal to the second gap.

(894) FIG. 156 is a plan view of one aspect of an end effector 6650. The end effector 6650 comprises a jaw member 6652 and a shaft 6654. The jaw member 6652 pivots about pivot point 6656 and defines a pivot angle. FIG. 157 is a side view of the end effector 6650 shown in FIG. 156 with a partial cut away view to expose the underlying structure of the jaw member 6652 and an ultrasonic blade 6658. An electrode 6660 is fixedly mounted to the jaw member 6652. The electrode 6660 is electrically coupled to the RF drive circuit 702 (FIG. 34) and is configured to apply RF energy to tissue located between the jaw member 6652 and the ultrasonic blade 6658. FIG. 158 is a partial sectional view of the end effector shown in FIGS. 156, 127 to expose the ultrasonic blade and right and left electrodes 6660a, 6660b, respectively. The jaw member 6652 and the ultrasonic blade 6658 are wider at a proximal end and are narrower at a distal end. Also, the jaw member 6652 and the ultrasonic blade 6658 define more curvature at a distal end relative to the proximal end. These features are clearly shown in the sectional views of FIGS. 159-164.

(895) FIG. 159 is a cross-sectional view taken at section 174-174 of the end effector 6650 shown in FIG. 156. The end effector 6650 comprises an ultrasonic blade 6658 acoustically coupled to an ultrasonic transducer which is electrically driven by the ultrasonic drive circuit 177 (FIG. 11). The

jaw member **6652** comprises an electrode **6660** comprising asymmetric electrodes **6660a**, **6660b**. A first electrode **6660a** is located on the right side and a second electrode **6660b** is located on the left side (from the perspective of the operator) of the jaw member **6652**. The right side electrode **6660a** defines a first width **W1** and defines a first gap **G1** between the electrode **6660a** and the ultrasonic blade **6658**. The left side electrode **6660b** defines a second width **W2** and defines a second gap **G2** between the electrode **6660b** and the ultrasonic blade **6658**. In one aspect the first width **W1** is less than the second width **W2** and the first gap **G1** is less than the second gap **G2**. With reference also to FIG. **158**, an electrically insulative element is disposed between the first and second electrodes **6660a**, **6660b**. In one aspect, the electrically insulative element comprising a soft polymeric pad **6662** located between the ultrasonic blade **6658** and the jaw member **6652** and a high density polymeric pad **6664** located adjacent the soft polymeric pad **6662** to prevent the ultrasonic blade **6658** from shorting the electrodes **6660a**, **6660b**. In one aspect, the soft and high density polymeric pads **6662**, **6664** can be made of polymers known under the tradename TEFLON (polytetrafluoroethylene polymers and copolymers), for example. Accordingly, the polymeric pads **6662**, **6664** may be made of soft TEFLON and high density TEFLON, respectively.

(896) FIG. **160** is cross-sectional view taken at section **175-175** of the end effector **6650** shown in FIG. **156**. At the plane where section **175-175** the end effector **6650** is thinner and has more curvature than section **174-174**. The right side electrode **6660a** defines a third width **W3** and defines a third gap **G3** between the electrode **6660a** and the ultrasonic blade **6658**. The left side electrode **6660b** defines a fourth width **W4** and defines a fourth gap **G4** between the electrode **6660b** and the ultrasonic blade **6658**. In one aspect the third width **W3** is less than the fourth width **W4** and the third gap **G3** is less than the fourth gap **G4**. In operation, tissue located in the gaps **G1**, **G2**, **G3**, **G4** defined between the electrodes **6660a**, **6660b** and the ultrasonic blade **6658** is sealed by high-frequency current transmitted through the electrodes **6660a**, **6660b**, the tissue, and the ultrasonic blade **6658**. The tissue located between the polymeric pad **6662** and the ultrasonic blade **6658** is cut by friction generated by the ultrasonic vibrations.

(897) FIG. **161** is a cross-sectional view taken at a section similar to section **174-174** of the end effector **6650** shown in FIG. **156**, except that the ultrasonic blade **6658'** has a different geometric configuration. The end effector **6650'** comprises an ultrasonic blade **6658'** acoustically coupled to an ultrasonic transducer which is electrically driven by the ultrasonic drive circuit **177** (FIG. **11**). The jaw member **6652'** comprises an electrode **6660'** comprising asymmetric electrodes **6660a'**, **6660b'**. A first electrode **6660a'** is located on the right side and a second electrode **6660b'** is located on the left side (from the perspective of the operator) of the jaw member **6652'**. The right side electrode **6660a'** defines a first width **W1** and defines a first gap **G1** between the electrode **6660a'** and the ultrasonic blade **6658'**. The left side electrode **6660b'** defines a second width **W2** and defines a second gap **G2** between the electrode **6660b'** and the ultrasonic blade **6658'**. In one aspect the first width **W1** is less than the second width **W2** and the first gap **G1** is less than the second gap **G2**. An electrically insulative element is disposed between the first and second electrodes **6660a'**, **6660b'**. In one aspect, the electrically insulative element comprises a soft polymeric pad **6662'** located adjacent to a high density polymeric pad **6664'** to prevent the ultrasonic blade **6658'** from shorting the electrodes **6660a'**, **6660b'**. In one aspect, the polymeric pads **6662'**, **6664'** can be made of polymers known under the tradename TEFLON (polytetrafluoroethylene polymers and copolymers), for example. In the aspect shown in FIGS. **176** and **177**, the ultrasonic blade **6658'** comprises features **6668'** suitable for cutting and features **6670'** suitable for coagulating tissue. The cutting features **6668'** define a smaller surface area relative to the coagulation features **6670'** to enable a more suitable cutting interface between the tissue and the ultrasonic blade **6658'**. The larger surface area of the coagulation features **6670'** are better suited to coagulation or seal tissue. Thus, in operation, tissue located between the electrodes **6660a'**, **6660b'** and the coagulation features **6670'** is sealed and tissue located between the cutting feature **6668'** and the polymeric pad **6662'** is cut.

(898) FIG. **162** is cross-sectional view taken at a section similar to section **175-175** of the end effector **6650** shown in FIG. **156**, except that the ultrasonic blade **6658'** has a different geometric configuration. At the plane where section **175-175** the end effector **6650'** is thinner and has more curvature than the end effector **6650'** at section **174-174**. The right side electrode **6660a'** defines a third width $W_{sub.3}$ and defines a third gap $G_{sub.3}$ between the electrode **6660a'** and the ultrasonic blade **6658'**. The left side electrode **6660b'** defines a fourth width $W_{sub.4}$ and defines a fourth gap $G_{sub.4}$ between the electrode **6660b'** and the ultrasonic blade **6658'**. In one aspect the third width $W_{sub.3}$ is less than the fourth width $W_{sub.4}$ and the third gap $G_{sub.3}$ is less than the fourth gap $G_{sub.4}$. In operation, tissue located in the gaps $G_{sub.1}$, $G_{sub.2}$, $G_{sub.3}$, $G_{sub.4}$ defined between the electrodes **6660a'**, **6660b'** and the ultrasonic blade **6658'** is sealed by high-frequency current transmitted through the electrodes **6660a'**, **6660b'**, the tissue, and the ultrasonic blade **6658'**. The tissue located between the polymeric pad **6662'** and the ultrasonic blade **6658'** is cut by friction generated by the ultrasonic vibrations.

(899) FIG. **163** is a cross-sectional view taken at a section similar to section **174-174** of the end effector **6650** shown in FIG. **156**, except that the ultrasonic blade **6658''** has a different geometric configuration. The end effector **6650''** comprises an ultrasonic blade **6658''** acoustically coupled to an ultrasonic transducer which is electrically driven by the ultrasonic drive circuit **177** (FIG. **11**). The jaw member **6652''** comprises an electrode **6660''** comprising asymmetric electrodes **6660a''**. A first electrode **6660a''** is located on the right side and a second electrode **6660b''** is located on the left side (from the perspective of the operator) of the jaw member **6652''**. The right side electrode **6660a''** defines a first width $W_{sub.1}$ and defines a first gap $G_{sub.1}$ between the electrode **6660a''** and the ultrasonic blade **6658''**. The left side electrode **6660b''** defines a second width $W_{sub.2}$ and defines a second gap $G_{sub.2}$ between the electrode **6660b''** and the ultrasonic blade **6658''**. In one aspect the first width $W_{sub.1}$ is less than the second width $W_{sub.2}$ and the first gap $G_{sub.1}$ is less than the second gap $G_{sub.2}$. An electrically insulative element is disposed between the first and second electrodes **6660a''**, **6660b''**. In one aspect, the electrically insulative element comprises a soft polymeric pad **6662''** located adjacent to a high density polymeric pad **6664''** to prevent the ultrasonic blade **6658''** from shorting the electrodes **6660a''**, **6660b''**. In one aspect, the polymeric pads **6662''**, **6664''** can be made of polymers known under the tradename TEFLON (polytetrafluoroethylene polymers and copolymers), for example.

(900) FIG. **164** is cross-sectional view taken at a section similar to section **175-175** of the end effector **6650** shown in FIG. **156**, except that the ultrasonic blade **6658''** has a different geometric configuration. At the plane where section **175-175** the end effector **6650''** is thinner and has more curvature than the end effector **6650''** at section **98-98**. The right side electrode **6660a''** defines a third width $W_{sub.3}$ and defines a third gap $G_{sub.3}$ between the electrode **6660a''** and the ultrasonic blade **6658''**. The left side electrode **6660b''** defines a fourth width $W_{sub.4}$ and defines a fourth gap $G_{sub.4}$ between the electrode **6660b''** and the ultrasonic blade **6658''**. In one aspect the third width $W_{sub.3}$ is less than the fourth width $W_{sub.4}$ and the third gap $G_{sub.3}$ is less than the fourth gap $G_{sub.4}$. In operation, tissue located in the gaps $G_{sub.1}$, $G_{sub.2}$, $G_{sub.3}$, $G_{sub.4}$ defined between the electrodes **6660a''**, **6660b''** and the ultrasonic blade **6658''** is sealed by high-frequency current transmitted through the electrodes **6660a''**, **6660b''**, the tissue, and the ultrasonic blade **6658''**. The tissue located between the polymeric pad **6662''** and the ultrasonic blade **6658''** is cut by friction generated by the ultrasonic vibrations. In the aspect shown in FIGS. **178** and **179**, the ultrasonic blade **6658''** comprises features **6668''** suitable for cutting and features **6670''** suitable for coagulating tissue. The cutting features **6668''** define a smaller surface area relative to the coagulation features **6670''** to enable a more suitable cutting interface between the tissue and the ultrasonic blade **6658''**. The larger surface area of the coagulation features **6670''** are better suited to coagulation or seal tissue. Thus, in operation, tissue located between the electrodes **6660a''**, **6660b''** and the coagulation features **6670''** is sealed and tissue located between the cutting feature **6668''** and the polymeric pad **6662''** is cut.

(901) The surgical instruments described herein also can include features to allow the energy being delivered by the ultrasonic drive circuit **177** (FIG. **11**) and the RF drive circuit **702** (FIG. **34**) to be dynamically adjusted or switched based on the type of tissue being treated by an end effector of a surgical instrument and various characteristics of the tissue. In one aspect, the power output from the ultrasonic drive circuit **177** and the RF drive circuit **702** that is delivered to the end effector of the surgical instrument can include an input that represents the tissue type to allow the energy profile of the from the ultrasonic drive circuit **177** and the RF drive circuit **702** to be dynamically changed during the procedure based on the type of tissue being effected by the end effector of the surgical instrument. As disclosed herein, techniques for controlling the ultrasonic drive circuit **177** (FIG. **11**) and the RF drive circuit **702** (FIG. **34**) based on the tissue type may be provided. Various techniques can be used to select a power profile to allow the energy being delivered from the ultrasonic drive circuit **177** and the RF drive circuit **702** to dynamically change based on the tissue type being treated by the surgical instrument.

(902) In one form, a strain gauge can be used to measure the force applied to the tissue by the end effector. A strain gauge can be coupled to the end effector to measure the force on the tissue being treated by the end effector. With reference now to FIG. **165**, a system **6680** for measuring forces applied to the tissue grasped by the end effector comprises a strain gauge sensor **6682**, such as, for example, a micro-strain gauge, is configured to measure one or more parameters of the end effector **6650**, **6650'**, **6650''** as shown in FIGS. **159-164**, for example. In one aspect, the strain gauge sensor **6682** can measure the amplitude or magnitude of the strain exerted on a jaw member of an end effector **6650**, **6650'**, **6650''** during a clamping operation, which can be indicative of the tissue compression. The measured strain is converted to a digital signal and provided to a processor **6690** of a microcontroller **6688**. A load sensor **6684** can measure the force to operate the ultrasonic blade **6658**, **6658'**, **6658''** as shown in FIGS. **159-164**, for example, to cut the tissue captured between the jaw member and the ultrasonic blade **6658**, **6658'**, **6658''** of the end effector **6650**, **6650'**, **6650''**. A magnetic field sensor **6686** can be employed to measure the thickness of the captured tissue **6678**. The measurement of the magnetic field sensor **6686** also may be converted to a digital signal and provided to the processor **6690**.

(903) Further to the above, a feedback indicator **6694** also can be configured to communicate with the microcontroller **6688**. In one aspect, the feedback indicator **6694** can be disposed in the handle of the combination ultrasonic/electrosurgical instruments **500**, **600**, **700** (FIGS. **30-44**).

Alternatively, the feedback indicator **6694** can be disposed in a shaft assembly of a surgical instrument, for example. In any event, the microcontroller **6688** may employ the feedback indicator **6694** to provide feedback to an operator of the surgical instrument with regard to the adequacy of a manual input such as, for example, a selected position of a firing trigger that is used to cause the end effector to clamp down on tissue. To do so, the microcontroller **6688** may assess the selected position of the jaw member **6672** and/or firing trigger. The measurements of the tissue **6678** compression, the tissue **6678** thickness, and/or the force required to close the end effector **6658**, **6658'**, **6658''** on the tissue, as respectively measured by the sensors **6682**, **6684**, **6686**, can be used by the microcontroller **6688** to characterize the selected position of the firing trigger and/or the corresponding value of the speed of end effector. In one instance, a memory **6692** may store a technique, an equation, and/or a look-up table which can be employed by the microcontroller **6688** in the assessment.

(904) In one aspect, the present disclosure provides an end effector for a surgical instrument, the end effector comprises an ultrasonic blade; and a jaw member comprising an asymmetric electrode comprising a first electrode and a second electrode; wherein the first electrode may define a first width and the second electrode may define a second width, wherein the first width is not equal to the second width; and wherein a first gap may be defined between the first electrode and the ultrasonic blade and a second gap may be defined between the second electrode and the ultrasonic blade, wherein the first gap is not equal to the second gap.

(905) The ultrasonic blade and the jaw member may define a curvature. The ultrasonic blade and the jaw member may define a greater curvature at a distal end relative to the curvature at a proximal end. The ultrasonic blade and the jaw member may define a greater width at a proximal end relative to a distal end. The end effector may further comprise an electrically insulative polymer pad disposed between the first and second electrodes. The electrically insulative polymer pad may comprise a first soft polymeric pad and a second and high density polymeric pad positioned adjacent to the soft polymeric pad. The ultrasonic blade may comprise features for cutting and features for coagulating tissue.

(906) In another aspect, the present disclosure provides a jaw member of an end effector for a surgical instrument, the jaw member comprising: an asymmetric electrode comprising a first electrode and a second electrode; wherein the first electrode may define a first width and the second electrode may define a second width, wherein the first width is not equal to the second width. The jaw member may define a curvature. The jaw member may define a greater curvature at a distal end relative to the curvature at a proximal end. The jaw member may define a greater width at a proximal end relative to a distal end. The jaw member may further comprise an electrically insulative polymer pad disposed between the first and second electrodes. The electrically insulative polymer pad may comprise a first soft polymeric pad and a second and high density polymeric pad positioned adjacent to the soft polymeric pad.

(907) In another aspect, the present disclosure provides, a surgical instrument, comprising a handle assembly; an end effector operably coupled to the hand assembly, the end effector comprising: an ultrasonic blade; and a jaw member comprising an asymmetric electrode comprising a first electrode and a second electrode; wherein the first electrode may define a first width and the second electrode may define a second width, wherein the first width is not equal to the second width; and wherein a first gap may be defined between the first electrode and the ultrasonic blade and a second gap may be defined between the second electrode and the ultrasonic blade, wherein the first gap is not equal to the second gap.

(908) The ultrasonic blade and the jaw member may define a curvature. The ultrasonic blade and the jaw member may define a greater curvature at a distal end relative to the curvature at a proximal end. The ultrasonic blade and the jaw member may define a greater width at a proximal end relative to a distal end.

(909) The surgical instrument may further comprise an electrically insulative polymer pad disposed between the first and second electrodes. The electrically insulative polymer pad may comprise a first soft polymeric pad and a second and high density polymeric pad positioned adjacent to the soft polymeric pad. The ultrasonic blade may comprise features for cutting and features for coagulating tissue.

(910) Aspects of the devices disclosed herein can be designed to be disposed of after a single use, or they can be designed to be used multiple times. Various aspects may, in either or both cases, be reconditioned for reuse after at least one use. Reconditioning may include any combination of the steps of disassembly of the device, followed by cleaning or replacement of particular pieces, and subsequent reassembly. In particular, aspects of the device may be disassembled, and any number of the particular pieces or parts of the device may be selectively replaced or removed in any combination. Upon cleaning and/or replacement of particular parts, aspects of the device may be reassembled for subsequent use either at a reconditioning facility, or by a surgical team immediately prior to a surgical procedure. Those skilled in the art will appreciate that reconditioning of a device may utilize a variety of techniques for disassembly, cleaning/replacement, and reassembly. Use of such techniques, and the resulting reconditioned device, are all within the scope of the present application.

(911) By way of example only, aspects described herein may be processed before surgery. First, a new or used instrument may be obtained and if necessary cleaned. The instrument may then be sterilized. In one sterilization technique, the instrument is placed in a closed and sealed container,

such as a plastic or TYVEK bag. The container and instrument may then be placed in a field of radiation that can penetrate the container, such as gamma radiation, x-rays, or high-energy electrons. The radiation may kill bacteria on the instrument and in the container. The sterilized instrument may then be stored in the sterile container. The sealed container may keep the instrument sterile until it is opened in a medical facility. A device may also be sterilized using any other technique known in the art, including but not limited to beta or gamma radiation, ethylene oxide, or steam.

(912) While various details have been set forth in the foregoing description, it will be appreciated that the various aspects of the techniques for operating a generator for digitally generating electrical signal waveforms and surgical instruments may be practiced without these specific details. One skilled in the art will recognize that the herein described components (e.g., operations), devices, objects, and the discussion accompanying them are used as examples for the sake of conceptual clarity and that various configuration modifications are contemplated. Consequently, as used herein, the specific exemplars set forth and the accompanying discussion are intended to be representative of their more general classes. In general, use of any specific exemplar is intended to be representative of its class, and the non-inclusion of specific components (e.g., operations), devices, and objects should not be taken limiting.

(913) Further, while several forms have been illustrated and described, it is not the intention of the applicant to restrict or limit the scope of the appended claims to such detail. Numerous modifications, variations, changes, substitutions, combinations, and equivalents to those forms may be implemented and will occur to those skilled in the art without departing from the scope of the present disclosure. Moreover, the structure of each element associated with the described forms can be alternatively described as a technique for providing the function performed by the element. Also, where materials are disclosed for certain components, other materials may be used. It is therefore to be understood that the foregoing description and the appended claims are intended to cover all such modifications, combinations, and variations as falling within the scope of the disclosed forms. The appended claims are intended to cover all such modifications, variations, changes, substitutions, modifications, and equivalents.

(914) For conciseness and clarity of disclosure, selected aspects of the foregoing disclosure have been shown in block diagram form rather than in detail. Some portions of the detailed descriptions provided herein may be presented in terms of instructions that operate on data that is stored in one or more computer memories or one or more data storage devices (e.g. floppy disk, hard disk drive, Compact Disc (CD), Digital Video Disk (DVD), or digital tape). Such descriptions and representations are used by those skilled in the art to describe and convey the substance of their work to others skilled in the art. In general, an algorithm refers to a self-consistent sequence of steps leading to a desired result, where a “step” refers to a manipulation of physical quantities and/or logic states which may, though need not necessarily, take the form of electrical or magnetic signals capable of being stored, transferred, combined, compared, and otherwise manipulated. It is common usage to refer to these signals as bits, values, elements, symbols, characters, terms, numbers, or the like. These and similar terms may be associated with the appropriate physical quantities and are merely convenient labels applied to these quantities and/or states.

(915) Unless specifically stated otherwise as apparent from the foregoing disclosure, it is appreciated that, throughout the foregoing disclosure, discussions using terms such as “processing” or “computing” or “calculating” or “determining” or “displaying” or the like, refer to the action and processes of a computer system, or similar electronic computing device, that manipulates and transforms data represented as physical (electronic) quantities within the computer system's registers and memories into other data similarly represented as physical quantities within the computer system memories or registers or other such information storage, transmission or display devices.

(916) In a general sense, those skilled in the art will recognize that the various aspects described

herein which can be implemented, individually and/or collectively, by a wide range of hardware, software, firmware, or any combination thereof can be viewed as being composed of various types of “electrical circuitry.” Consequently, as used herein “electrical circuitry” includes, but is not limited to, electrical circuitry having at least one discrete electrical circuit, electrical circuitry having at least one integrated circuit, electrical circuitry having at least one application specific integrated circuit, electrical circuitry forming a general purpose computing device configured by a computer program (e.g., a general purpose computer configured by a computer program which at least partially carries out processes and/or devices described herein, or a microprocessor configured by a computer program which at least partially carries out processes and/or devices described herein), electrical circuitry forming a memory device (e.g., forms of random access memory), and/or electrical circuitry forming a communications device (e.g., a modem, communications switch, or optical-electrical equipment). Those having skill in the art will recognize that the subject matter described herein may be implemented in an analog or digital fashion or some combination thereof.

(917) The foregoing detailed description has set forth various forms of the devices and/or processes via the use of block diagrams, flowcharts, and/or examples. Insofar as such block diagrams, flowcharts, and/or examples contain one or more functions and/or operations, it will be understood by those within the art that each function and/or operation within such block diagrams, flowcharts, and/or examples can be implemented, individually and/or collectively, by a wide range of hardware, software, firmware, or virtually any combination thereof. In one form, several portions of the subject matter described herein may be implemented via an application specific integrated circuits (ASIC), a field programmable gate array (FPGA), a digital signal processor (DSP), or other integrated formats. However, those skilled in the art will recognize that some aspects of the forms disclosed herein, in whole or in part, can be equivalently implemented in integrated circuits, as one or more computer programs running on one or more computers (e.g., as one or more programs running on one or more computer systems), as one or more programs running on one or more processors (e.g., as one or more programs running on one or more microprocessors), as firmware, or as virtually any combination thereof, and that designing the circuitry and/or writing the code for the software and or firmware would be well within the skill of one of skill in the art in light of this disclosure. In addition, those skilled in the art will appreciate that the mechanisms of the subject matter described herein are capable of being distributed as one or more program products in a variety of forms, and that an illustrative form of the subject matter described herein applies regardless of the particular type of signal bearing medium used to actually carry out the distribution. Examples of a signal bearing medium include, but are not limited to, the following: a recordable type medium such as a floppy disk, a hard disk drive, a Compact Disc (CD), a Digital Video Disk (DVD), a digital tape, a computer memory, etc.; and a transmission type medium such as a digital and/or an analog communication medium (e.g., a fiber optic cable, a waveguide, a wired communications link, a wireless communication link (e.g., transmitter, receiver, transmission logic, reception logic, etc.), etc.).

(918) In some instances, one or more elements may be described using the expression “coupled” and “connected” along with their derivatives. It should be understood that these terms are not intended as synonyms for each other. For example, some aspects may be described using the term “connected” to indicate that two or more elements are in direct physical or electrical contact with each other. In another example, some aspects may be described using the term “coupled” to indicate that two or more elements are in direct physical or electrical contact. The term “coupled,” however, also may mean that two or more elements are not in direct contact with each other, but yet still co-operate or interact with each other. It is to be understood that depicted architectures of different components contained within, or connected with, different other components are merely examples, and that in fact many other architectures may be implemented which achieve the same functionality. In a conceptual sense, any arrangement of components to achieve the same

functionality is effectively “associated” such that the desired functionality is achieved. Hence, any two components herein combined to achieve a particular functionality can be seen as “associated with” each other such that the desired functionality is achieved, irrespective of architectures or intermedial components. Likewise, any two components so associated also can be viewed as being “operably connected,” or “operably coupled,” to each other to achieve the desired functionality, and any two components capable of being so associated also can be viewed as being “operably couplable,” to each other to achieve the desired functionality. Specific examples of operably couplable include but are not limited to physically mateable and/or physically interacting components, and/or wirelessly interactable, and/or wirelessly interacting components, and/or logically interacting, and/or logically interactable components, and/or electrically interacting components, and/or electrically interactable components, and/or optically interacting components, and/or optically interactable components.

(919) In other instances, one or more components may be referred to herein as “configured to,” “configurable to,” “operable/operative to,” “adapted/adaptable,” “able to,” “conformable/conformed to,” etc. Those skilled in the art will recognize that “configured to” can generally encompass active-state components and/or inactive-state components and/or standby-state components, unless context requires otherwise.

(920) While particular aspects of the present disclosure have been shown and described, it will be apparent to those skilled in the art that, based upon the teachings herein, changes and modifications may be made without departing from the subject matter described herein and its broader aspects and, therefore, the appended claims are to encompass within their scope all such changes and modifications as are within the true scope of the subject matter described herein. It will be understood by those within the art that, in general, terms used herein, and especially in the appended claims (e.g., bodies of the appended claims) are generally intended as “open” terms (e.g., the term “including” should be interpreted as “including but not limited to,” the term “having” should be interpreted as “having at least,” the term “includes” should be interpreted as “includes but is not limited to,” etc.). It will be further understood by those within the art that if a specific number of an introduced claim recitation is intended, such an intent will be explicitly recited in the claim, and in the absence of such recitation no such intent is present. For example, as an aid to understanding, the following appended claims may contain usage of the introductory phrases “at least one” and “one or more” to introduce claim recitations. However, the use of such phrases should not be construed to imply that the introduction of a claim recitation by the indefinite articles “a” or “an” limits any particular claim containing such introduced claim recitation to claims containing only one such recitation, even when the same claim includes the introductory phrases “one or more” or “at least one” and indefinite articles such as “a” or “an” (e.g., “a” and/or “an” should typically be interpreted to mean “at least one” or “one or more”); the same holds true for the use of definite articles used to introduce claim recitations.

(921) In addition, even if a specific number of an introduced claim recitation is explicitly recited, those skilled in the art will recognize that such recitation should typically be interpreted to mean at least the recited number (e.g., the bare recitation of “two recitations,” without other modifiers, typically technique at least two recitations, or two or more recitations). Furthermore, in those instances where a convention analogous to “at least one of A, B, and C, etc.” is used, in general such a construction is intended in the sense one having skill in the art would understand the convention (e.g., “a system having at least one of A, B, and C” would include but not be limited to systems that have A alone, B alone, C alone, A and B together, A and C together, B and C together, and/or A, B, and C together, etc.). In those instances where a convention analogous to “at least one of A, B, or C, etc.” is used, in general such a construction is intended in the sense one having skill in the art would understand the convention (e.g., “a system having at least one of A, B, or C” would include but not be limited to systems that have A alone, B alone, C alone, A and B together, A and C together, B and C together, and/or A, B, and C together, etc.). It will be further understood by

those within the art that typically a disjunctive word and/or phrase presenting two or more alternative terms, whether in the description, claims, or drawings, should be understood to contemplate the possibilities of including one of the terms, either of the terms, or both terms unless context dictates otherwise. For example, the phrase “A or B” will be typically understood to include the possibilities of “A” or “B” or “A and B.”

(922) With respect to the appended claims, those skilled in the art will appreciate that recited operations therein may generally be performed in any order. Also, although various operational flows are presented in a sequence(s), it should be understood that the various operations may be performed in other orders than those which are illustrated, or may be performed concurrently. Examples of such alternate orderings may include overlapping, interleaved, interrupted, reordered, incremental, preparatory, supplemental, simultaneous, reverse, or other variant orderings, unless context dictates otherwise. Furthermore, terms like “responsive to,” “related to,” or other past-tense adjectives are generally not intended to exclude such variants, unless context dictates otherwise.

(923) It is worthy to note that any reference to “one aspect,” “an aspect,” “one form,” or “a form” technique that a particular feature, structure, or characteristic described in connection with the aspect is included in at least one aspect. Thus, appearances of the phrases “in one aspect,” “in an aspect,” “in one form,” or “in an form” in various places throughout the specification are not necessarily all referring to the same aspect. Furthermore, the particular features, structures or characteristics may be combined in any suitable manner in one or more aspects.

(924) With respect to the use of substantially any plural and/or singular terms herein, those having skill in the art can translate from the plural to the singular and/or from the singular to the plural as is appropriate to the context and/or application. The various singular/plural permutations are not expressly set forth herein for sake of clarity.

(925) In certain cases, use of a system or method may occur in a territory even if components are located outside the territory. For example, in a distributed computing context, use of a distributed computing system may occur in a territory even though parts of the system may be located outside of the territory (e.g., relay, server, processor, signal-bearing medium, transmitting computer, receiving computer, etc. located outside the territory).

(926) A sale of a system or method may likewise occur in a territory even if components of the system or method are located and/or used outside the territory. Further, implementation of at least part of a system for performing a method in one territory does not preclude use of the system in another territory.

(927) All of the above-mentioned U.S. patents, U.S. patent application publications, U.S. patent applications, foreign patents, foreign patent applications, non-patent publications referred to in this specification and/or listed in any Application Data Sheet, or any other disclosure material are incorporated herein by reference, to the extent not inconsistent herewith. As such, and to the extent necessary, the disclosure as explicitly set forth herein supersedes any conflicting material incorporated herein by reference. Any material, or portion thereof, that is said to be incorporated by reference herein, but which conflicts with existing definitions, statements, or other disclosure material set forth herein will only be incorporated to the extent that no conflict arises between that incorporated material and the existing disclosure material.

(928) In summary, numerous benefits have been described which result from employing the concepts described herein. The foregoing description of the one or more forms has been presented for purposes of illustration and description. It is not intended to be exhaustive or limiting to the precise form disclosed. Modifications or variations are possible in light of the above teachings. The one or more forms were chosen and described in order to illustrate principles and practical application to thereby enable one of ordinary skill in the art to utilize the various forms and with various modifications as are suited to the particular use contemplated. It is intended that the claims submitted herewith define the overall scope.

Claims

1. A surgical instrument comprising: a handle assembly coupled to a proximal end of a shaft assembly; the shaft assembly coupled to a distal end of the handle assembly; and an end effector coupled to a distal end of the shaft assembly, and comprising: a first jaw and a second jaw configured for pivotal movement between a closed position and an open position; and a segmented flexible circuit fixedly attached to the first jaw and positioned between the first jaw and the second jaw such that the segmented flexible circuit touches tissue when the first jaw and the second jaw close onto the tissue; the segmented flexible circuit comprising: a plurality of segments comprising a distal segment fixedly attached to a distal end of the first jaw, and a plurality of lateral segments fixedly attached to lateral sides of the first jaw; wherein each segment of the plurality of segments comprises an electrode, an electrical insulation, a compressive layer, a laminate layer, and a plurality of data sensors positioned intermediate the electrode and the first jaw, wherein the plurality of data sensors comprises a temperature sensor and two force sensors, wherein the electrical insulation is positioned between the electrode and the temperature sensor, wherein the temperature sensor is positioned between the electrical insulation and one of the force sensors, wherein the one of the force sensors is positioned between the temperature sensor and the compressive layer, wherein the compressive layer is positioned between the one of the force sensors and the other of the force sensors, wherein the other of the force sensors is positioned between the compressive layer and the laminate layer, wherein the laminate layer is positioned between the other of the force sensors and the first jaw; a plurality of electrical connectors, wherein the plurality of electrical connectors electrically couples the plurality of segments to an energy source; and wherein each segment of the plurality of segments is individually addressable to treat the tissue by providing a first power level from the energy source to a first electrode of a first segment of the plurality of segments without providing the first power level to a second electrode of a second segment of the plurality of segments, and wherein an amount of power provided to each of the plurality of segments is determined based on data provided by the plurality of data sensors corresponding to each segment of the plurality of segments.
2. The surgical instrument of claim 1, wherein the end effector further comprises: a Hall effect sensor positioned at a distal end of one of the first jaw or the second jaw, and a magnet in the other of the first jaw and the second jaw; wherein the combination of the Hall effect sensor and the magnet are configured to measure an aperture between the first jaw and the second jaw.
3. The surgical instrument of claim 1, wherein the plurality of lateral segments comprises a first lateral segment located adjacent to the distal segment and a second lateral segment located at the proximal end of the end effector and adjacent to the first lateral segment.
4. The surgical instrument of claim 1, wherein the second jaw comprises an ultrasonic blade.
5. The surgical instrument of claim 1, wherein the plurality of data sensors of each of the plurality of segments are configured to detect a presence of tissue positioned between the second jaw and itself.
6. The surgical instrument of claim 5, wherein the energy source is configured to individually provide energy to each of the plurality of segments after it is detected that tissue is positioned between the second jaw and each of the plurality of segments.
7. The surgical instrument of claim 5, wherein the plurality of data sensors of at least one of the plurality of segments comprises a Hall effect sensor configured to detect a thickness of tissue positioned between the second jaw and itself.
8. The surgical instrument of claim 5, wherein the force sensor is configured to detect a force applied to the tissue positioned between the second jaw and itself.
9. The surgical instrument of claim 5, wherein the temperature sensor is configured to detect a temperature of the tissue positioned between the second jaw and itself.

10. The surgical instrument of claim 1, wherein the first jaw comprises a left side and a right side, and the first segment is positioned on the left side of the first jaw and adjacent to the distal segment, and the second segment is positioned on the right side of the first jaw and adjacent to the distal segment.

11. The surgical instrument of claim 10, wherein the electrode of the first segment is configured to apply RF energy from the energy source at the first power level, based on a first sensed characteristic about the tissue positioned at the plurality of data sensors of the first segment, and the second segment is configured to simultaneously apply RF energy from the energy source at a second power level that is different than the first power level, based on a second sensed characteristic about the tissue positioned at the plurality of data sensors of the second segment, wherein the second sensed characteristic is different than the first sensed characteristic.

12. An end effector of a surgical instrument comprising: a first jaw and a second jaw configured for pivotal movement between a closed position and an open position; and a segmented flexible circuit configured to fixedly attach to the first jaw positioned between the first jaw and the second jaw such that the segmented flexible circuit touches tissue when the first jaw and the second jaw close onto the tissue; the segmented flexible circuit comprising: a plurality of segments, wherein the plurality of segments comprises a distal segment configured to fixedly attach to a distal end of the first jaw, a plurality of lateral segments configured to fixedly attach to lateral sides of the first jaw; wherein each segment of the plurality of segments comprises an electrode, an electrical insulation, a compressive layer, a laminate layer, and a plurality of data sensors positioned intermediate the electrode and the first jaw, wherein the plurality of data sensors comprises a temperature sensor and two force sensors, wherein the electrical insulation is positioned between the electrode and the temperature sensor, wherein the temperature sensor is positioned between the electrical insulation and one of the force sensors, wherein the one of the force sensors is positioned between the temperature sensor and the compressive layer, wherein the compressive layer is positioned between the one of the force sensors and the other of the force sensors, wherein the other of the force sensors is positioned between the compressive layer and the laminate layer, wherein the laminate layer is positioned between the other of the force sensors and the first jaw; and a plurality of electrical connectors, wherein the plurality of electrical connectors electrically couples the plurality of segments to an energy source on a proximal end; wherein the plurality of segments are each individually addressable to treat tissue by providing a first power level from the energy source to a first electrode of a first segment of the plurality of segments without providing the first power level to a second electrode of a second segment of the plurality of segments, and wherein an amount of power provided to each of the plurality of segments is determined based on data provided by the plurality of data sensors corresponding to each of the plurality of segments.

13. The end effector of claim 12, further comprising: a Hall effect sensor positioned at a distal end of one of the first jaw or the second jaw, and a magnet in the other of the first jaw and the second jaw; wherein the combination of the Hall effect sensor and the magnet are configured to measure an aperture between the first jaw and the second jaw.

14. The end effector of claim 12, wherein the plurality of lateral segments comprises a first lateral segment located adjacent to the distal segment and a second lateral segment located at the proximal end of the end effector and adjacent to the first lateral segment.

15. The end effector of claim 12, wherein the plurality of data sensors of each of the plurality of segments configured to detect a presence of tissue positioned between the second jaw and itself.

16. The end effector of claim 15, wherein the energy source is configured to individually provide energy to each of the plurality of segments after it is detected that tissue is positioned between the second jaw and each of the plurality of segments.

17. The end effector of claim 12, wherein: the first jaw comprises a left side and a right side; the first segment is positioned on the left side of the first jaw and adjacent to the distal segment, and the second segment is positioned on the right side of the first jaw and adjacent to the distal

segment; the electrode of the first segment is configured to apply RF energy from the energy source at a first power level, based on a first sensed characteristic about the tissue positioned at the first segment; and the second segment is configured to simultaneously apply RF energy from the energy source at a second power level that is different than the first power level, based on a second sensed characteristic about the tissue positioned at the plurality of data sensors of the second segment, wherein the second sensed characteristic is different than the first sensed characteristic.
