

US Patent & Trademark Office

Patent Public Search | Text View

United States Patent Application Publication

20250287644

Kind Code

A1

Publication Date

September 11, 2025

Inventor(s)

YAMAZAKI; Shunpei

SEMICONDUCTOR DEVICE

Abstract

A semiconductor device that can operate at high speed or having high strength against stress is provided. One embodiment of the present invention is a semiconductor device including a semiconductor film including a channel formation region and a pair of impurity regions between which the channel formation region is positioned; a gate electrode overlapping side and top portions of the channel formation region with an insulating film positioned between the gate electrode and the side and top portions; and a source electrode and a drain electrode in contact with side and top portions of the pair of impurity regions.

Inventors: YAMAZAKI; Shunpei (Tokyo, JP)

Applicant: SEMICONDUCTOR ENERGY LABORATORY CO., LTD. (Atsugi-shi, JP)

Family ID: 1000008629100

Appl. No.: 19/220389

Filed: May 28, 2025

Foreign Application Priority Data

JP	2013-190275	Sep. 13, 2013
----	-------------	---------------

Related U.S. Application Data

parent US continuation 18398373 20231228 PENDING child US 19220389

parent US continuation 17982566 20221108 parent-grant-document US 11869977 child US 18398373

parent US continuation 17062697 20201005 parent-grant-document US 11508852 child US 17982566

parent US continuation 15614694 20170606 parent-grant-document US 10797179 child US 17062697

Publication Classification

Int. Cl.: **H10D30/67** (20250101); **G02F1/1368** (20060101); **H10D30/62** (20250101)

U.S. Cl.:

CPC **H10D30/6734** (20250101); **H10D30/62** (20250101); **H10D30/6219** (20250101);
H10D30/6729 (20250101); **H10D30/675** (20250101); **H10D30/6757** (20250101);
G02F1/1368 (20130101)

Background/Summary

CROSS-REFERENCE TO RELATED APPLICATIONS [0001] This application is a continuation of U.S. application Ser. No. 18/398,373, filed Dec. 28, 2023, now allowed, which is a continuation of U.S. application Ser. No. 17/982,566, filed Nov. 8, 2022, now U.S. Pat. No. 11,869,977, which is a continuation of U.S. application Ser. No. 17/062,697, filed Oct. 5, 2020, now U.S. Pat. No. 11,508,852, which is a continuation of U.S. application Ser. No. 15/614,694, filed Jun. 6, 2017, now U.S. Pat. No. 10,797,179, which is a continuation of U.S. application Ser. No. 14/391,024, filed Oct. 7, 2014, now U.S. Pat. No. 9,680,026, which is a U.S. National Phase of International Patent Application No. PCT/JP2014/074155, filed Sep. 5, 2014, which claims the benefit of a foreign priority application filed in Japan as Serial No. 2013-190275 on Sep. 13, 2013, all of which are incorporated by reference.

TECHNICAL FIELD

[0002] The present invention relates to an object, a method, or a manufacturing method. In addition, the present invention relates to a process, a machine, manufacture, or a composition of matter. In particular, one embodiment of the present invention relates to a semiconductor device, a display device, a light-emitting device, a memory device, a driving method thereof, or a manufacturing method thereof. Specifically, one embodiment of the present invention relates to a semiconductor device utilizing semiconductor characteristics.

BACKGROUND ART

[0003] Semiconductor display devices used in portable electronic appliances have been required to reduce an area other than a pixel portion (i.e., to narrow a bezel width). A system-on-panel obtained by forming a pixel portion and some of or all driver circuits over one substrate is one of effective means for achieving a narrow bezel width.

[0004] Patent Document 1 described below discloses a system-on-panel display device in which a display portion and peripheral circuits are formed on one substrate.

Patent Document

[0005] [Patent Document 1] Japanese Published Patent Application No. 2009-151293

DISCLOSURE OF INVENTION

[0006] Meanwhile, the number of pixels of an active-matrix semiconductor display device has been increased in order to display an image with higher definition and higher resolution. Therefore, higher speed operation is required for driver circuits such as a scan line driver circuit and a signal line driver circuit. In particular, a signal line driver circuit has even higher driving frequency than a scan line driver circuit because when pixels in a line are selected, an image signal needs to be supplied to all the pixels in the line.

[0007] Furthermore, use of a flexible material such as plastic for a substrate of a semiconductor device can widen the application range of the semiconductor device. In the case where a flexible substrate is used, high stress resistance is needed for a semiconductor element as compared to the case where a substrate that is poor in flexibility, such as a glass substrate, is used.

[0008] In view of the above technical background, an object of one embodiment of the present invention is to provide a semiconductor device that can operate at high speed. Another object of one embodiment of the present invention is to provide a semiconductor device having high strength against stress. An object of one embodiment of the present invention is to provide a novel semiconductor device. Note that the descriptions of these objects do not disturb the existence of other objects. In one embodiment of the present invention, there is no need to achieve all the objects. Other objects will be apparent from and can be derived from the description of the specification, the drawings, the claims, and the like.

[0009] A semiconductor device of one embodiment of the present invention includes a semiconductor film including a channel formation region and a pair of impurity regions between which the channel formation region is positioned; an insulating film covering side and top portions of the semiconductor film in the channel formation region; a gate electrode overlapping the side and top portions of the semiconductor film in the channel formation region with the insulating film positioned between the gate electrode and the side and top portions; and a source electrode and a drain electrode in contact with side and top portions of the semiconductor film in the pair of impurity regions.

[0010] A semiconductor device of one embodiment of the present invention includes a first gate electrode; a first insulating film covering the first gate electrode; a semiconductor film including a channel formation region overlapping the first gate electrode with the first insulating film positioned between the channel formation region and the first gate electrode, and a pair of impurity regions between which the channel formation region is positioned; a second insulating film covering side and top portions of the semiconductor film in the channel formation region; a second gate electrode overlapping the side and top portions of the semiconductor film with the second insulating film positioned between the second gate electrode and the side and top portions; and a source electrode and a drain electrode in contact with side and top portions of the semiconductor film in the pair of impurity regions.

[0011] A semiconductor device of one embodiment of the present invention includes a first gate electrode; a first insulating film covering the first gate electrode; a semiconductor film including a channel formation region overlapping the first gate electrode with the first insulating film positioned between the channel formation region and the first gate electrode, and a pair of impurity regions between which the channel formation region is positioned; a second insulating film covering side and top portions of the semiconductor film in the channel formation region; a second gate electrode overlapping the side and top portions of the semiconductor film with the second insulating film positioned between the second gate electrode and the side and top portions, and connected to the first gate electrode through an opening portion included in the first insulating film and the second insulating film; and a source electrode and a drain electrode in contact with side and top portions of the semiconductor film in the pair of impurity regions.

[0012] According to one embodiment of the present invention, a semiconductor device that can operate at high speed can be provided. According to one embodiment of the present invention, a semiconductor device having high strength against stress can be provided. According to one embodiment of the present invention, a novel semiconductor device, a novel display device, a novel light-emitting device, or the like can be provided. Note that the description of these effects does not disturb the existence of other effects. One embodiment of the present invention does not necessarily achieve all the objects listed above. Other effects will be apparent from and can be derived from the description of the specification, the drawings, the claims, and the like.

Description

BRIEF DESCRIPTION OF DRAWINGS

[0013] FIGS. 1A to 1D illustrate a structure of a transistor.
[0014] FIGS. 2A to 2D illustrate a structure of a transistor.
[0015] FIGS. 3A to 3D illustrate a structure of a transistor.
[0016] FIGS. 4A to 4D illustrate a structure of a transistor.
[0017] FIGS. 5A to 5D illustrate a structure of a transistor.
[0018] FIGS. 6A to 6D illustrate a structure of a transistor.
[0019] FIGS. 7A to 7D illustrate a structure of a transistor.
[0020] FIG. 8 illustrates structures of transistors.
[0021] FIG. 9 illustrates structures of transistors.
[0022] FIGS. 10A and 10B illustrate a method for manufacturing a semiconductor device.
[0023] FIGS. 11A and 11B illustrate a method for manufacturing a semiconductor device.
[0024] FIGS. 12A and 12B illustrate a method for manufacturing a semiconductor device.
[0025] FIGS. 13A and 13B illustrate a method for manufacturing a semiconductor device.
[0026] FIGS. 14A to 14C each illustrate a structure of a semiconductor display device.
[0027] FIG. 15 is a top view of a pixel.
[0028] FIG. 16 is a cross-sectional view of a light-emitting device.
[0029] FIGS. 17A and 17B show structures of sequential circuits.
[0030] FIG. 18 illustrates a configuration of a signal line driver circuit;
[0031] FIG. 19 illustrates a configuration of a scan line driver circuit.
[0032] FIG. 20 is a perspective view of a light-emitting device.
[0033] FIGS. 21A to 21F each illustrate an electronic appliance.

BEST MODE FOR CARRYING OUT THE INVENTION

[0034] Embodiments of the present invention will be described below in detail with reference to the drawings. Note that the present invention is not limited to the following description. Note that the present invention is not limited to the following description, and it is easily understood by those skilled in the art that the mode and details can be variously changed without departing from the spirit and scope of the present invention. Therefore, the present invention should not be construed as being limited to the description of the embodiments below.

[0035] Note that one embodiment of the present invention includes, in its category, any semiconductor device using transistors, for example, integrated circuits, RF tags, and semiconductor display devices. The integrated circuits include, in its category, large scale integrated circuits (LSIs) including a microprocessor, an image processing circuit, a digital signal processor (DSP), a microcontroller, and the like, and programmable logic devices (PLDs) such as a field programmable gate array (FPGA) and a complex PLD (CPLD). In addition, the semiconductor display devices include, in its category, liquid crystal display devices, light-emitting devices in which a light-emitting element typified by an organic light-emitting element (OLED) is provided for each pixel, electronic papers, digital micromirror devices (DMDs), plasma display panels (PDPs), field emission displays (FEDs), and other semiconductor display devices in which a transistor is included in a driver circuit.

[0036] In this specification, the semiconductor display device includes, in its category, panels in which a display element such as a liquid crystal element or a light-emitting element is provided for each pixel, and modules in which an IC or the like including a controller is mounted on the panel. Furthermore, an element substrate corresponding to one mode before a display element is completed in a manufacturing process of a semiconductor display device falls into the category of the semiconductor display device of one embodiment of the present invention. In the element substrate, each of a plurality of pixels is provided with a transistor, electrodes used for a display

element, such as a pixel electrode and a common electrode, and a capacitor.

[0037] In addition, the semiconductor display device of one embodiment of the present invention may include a touch panel which is a position input device capable of detecting a position pointed at with a finger, a stylus, or the like and generating a signal including the positional information.

[0038] Note that the term “connection” in this specification means electrical connection and corresponds to the case of a configuration in which current, voltage, or potential can be supplied or transmitted. Therefore, a configuration in which a circuit and another circuit are connected does not necessarily refers to a configuration in which they are directly connected, and also includes a configuration in which they are indirectly connected through an element such as a wiring, a resistor, a diode, or transistor so that current, voltage and potential can be supplied or transmitted. Furthermore, a configuration in which an element and another element are connected does not necessarily refers to a configuration in which they are directly connected, and also includes a configuration in which they are indirectly connected through an element such as a wiring, a resistor, diode, or a transistor so that current, voltage, or potential can be supplied to transmitted. In addition, even when different components are connected to each other in a circuit diagram, there is actually a case where one conductive film has functions of a plurality of components such as a case where part of a wiring serves as an electrode. The term “connection” in this specification also means such a case where one conductive film has functions of a plurality of components.

[0039] Note that a “source” of a transistor means a source region that is part of a semiconductor film functioning as an active layer or a source electrode connected to the semiconductor film.

Similarly, a “drain” of the transistor means a drain region that is part of the semiconductor film or a drain electrode connected to the semiconductor film. A “gate” means a gate electrode.

[0040] The terms “source” and “drain” of a transistor interchange with each other depending on the type of the channel of the transistor or levels of potentials applied to the terminals. In general, in an n-channel transistor, a terminal to which a lower potential is applied is called a source, and a terminal to which a higher potential is applied is called a drain. Furthermore, in a p-channel transistor, a terminal to which a lower potential is applied is called a drain, and a terminal to which a higher potential is applied is called a source. In this specification, although connection relation of the transistor is described assuming that the source and the drain are fixed in some cases for convenience, actually, the names of the source and the drain interchange with each other depending on the relation of the potentials.

Structure Example 1 of Transistor

[0041] FIGS. **1A** to **1D** illustrate a structure example of a transistor **10** included in a semiconductor device of one embodiment of the present invention. FIG. **1A** is a plan view of the transistor **10**.

Note that to clarify the layout of the transistor **10**, a variety of insulating films are omitted in FIG. **1A**. FIG. **1B** shows a circuit symbol of the transistor **10** illustrated in FIG. **1A**. FIG. **1C** is a cross-sectional view taken along dashed line A1-A2 in the plan view in FIG. **1A**. FIG. **1D** is a cross-sectional view taken along dashed line B1-B2 in the plan view in FIG. **1A**.

[0042] The transistor **10** illustrated in FIGS. **1A**, **1C**, and **1D** includes a semiconductor film **12** over a substrate **11** having an insulating surface. The semiconductor film **12** includes a channel formation region **12a** and impurity regions **12b** and **12c** between which the channel formation region **12a** is positioned. Furthermore, the transistor **10** includes an insulating film **13** that functions as a gate insulating film and covers side and top portions of the semiconductor film **12** in the channel formation region **12a**. In addition, the transistor **10** includes a conductive film **17** that functions as a gate electrode (FG) denoted by a circuit symbol in FIG. **1B**, and overlaps side and top portions of the semiconductor film **12** in the channel formation region **12a** with the insulating film **13** positioned therebetween. Moreover, the transistor **10** includes conductive films **14** and **15** that function as a source electrode(S) and a drain electrode (D) denoted by circuit symbols in FIG. **1B**, and are connected to side and top portions of the semiconductor film **12** in the impurity regions **12b** and **12c**.

[0043] Note that at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is provided on at least part (or all) of a surface, a side surface, a top surface, and/or a bottom surface of the semiconductor film **12**.

[0044] Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is in contact with at least part (or all) of the surface, the side surface, the top surface, and/or the bottom surface of the semiconductor film **12**. Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is in contact with at least part (or all) of the semiconductor film **12**.

[0045] Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is electrically connected to at least part (or all) of the surface, the side surface, the top surface, and/or the bottom surface of the semiconductor film **12**. Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is electrically connected to at least part (or all) of the semiconductor film **12**.

[0046] Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is provided near at least part (or all) of the surface, the side surface, the top surface, and/or the bottom surface of the semiconductor film **12**. Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is provided near at least part (or all) of the semiconductor film **12**.

[0047] Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is provided on a side of at least part (or all) of the surface, the side surface, the top surface, and/or the bottom surface of the semiconductor film **12**. Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is provided on a side of at least part (or all) of the semiconductor film **12**.

[0048] Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is provided obliquely above at least part (or all) of the surface, the side surface, the top surface, and/or the bottom surface of the semiconductor film **12**. Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is provided obliquely above at least part (or all) of the semiconductor film **12**.

[0049] Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is provided above at least part (or all) of the surface, the side surface, the top surface, and/or the bottom surface of the semiconductor film **12**. Alternatively, at least part (or all) of the conductive film **14** (and/or the conductive film **15**) is provided above at least part (or all) of the semiconductor film **12**.

[0050] FIGS. **1A**, **1C**, and **1D** illustrate an example in which an insulating film **16** is provided over the semiconductor film **12**, the insulating film **13**, and the conductive film **17**, and the conductive films **14** and **15** are provided over the insulating film **16**. Furthermore, in FIGS. **1A**, **1C**, and **1D**, the conductive films **14** and **15** are connected to the impurity regions **12b** and **12c** through opening portions **18** and **19** of the insulating film **16**, respectively.

[0051] As illustrated in FIGS. **1A** to **1D**, in the transistor **10** of one embodiment of the present invention, the side and top portions of the semiconductor film **12** in the channel formation region **12a** and the conductive film **17** overlap each other, whereby carriers flow in a wide range including the side and top portions of the channel formation region **12a**. Therefore, an area on the substrate occupied by the channel formation region **12a** of the semiconductor film **12** can be reduced and the amount of carriers transferred in the transistor **10** can be increased. As a result, the on-state current of the transistor **10** is increased and the field-effect mobility of the transistor **10** is also increased. On the assumption that the length of the semiconductor film **12** in the channel formation region **12a** in the channel width direction (the channel width) is W , and the thickness of the semiconductor film **12** in the channel formation region **12a** is T , when the aspect ratio that corresponds to the ratio of the thickness T to the channel width W is high, a region where carrier flows becomes wider. Thus, the on-state current of the transistor **10** is further increased and the field-effect mobility of

the transistor **10** is further increased. Note that in this specification, the aspect ratio refers to the ratio (T/W) of the thickness (T) of a semiconductor film to the length of a short side of a bottom surface (channel width W) of the semiconductor layer.

[0052] Unlike in the case of a transistor using a bulk semiconductor substrate, in the case of the transistor **10** using the semiconductor film **12** that is a thin film, the aspect ratio is preferably such that the high crystallinity of the semiconductor film **12** can be ensured. In the case where the semiconductor film **12** contains silicon or the case where the semiconductor film **12** contains silicon and germanium, in consideration of ensuring the high crystallinity of the semiconductor film **12**, specifically, the thickness T is preferably greater than or equal to 5 nm and less than or equal to 150 nm, and further preferably greater than or equal to 20 nm and less than or equal to 100 nm. On the assumption that the thickness T falls within the above range, in consideration of the resolution of an exposure apparatus which is approximately several micrometers in the case of using a glass substrate, the specific aspect ratio is preferably greater than or equal to 0.05 and less than or equal to 10, and further preferably greater than or equal to 0.1 and less than or equal to 5, and still further preferably greater than or equal to 1 and less than or equal to 5.

[0053] The channel length direction refers to a direction in which carriers are transferred at the shortest distance between the impurity regions **12b** and **12c**. The channel width direction refers to a direction perpendicular to the channel length direction.

[0054] Furthermore, as illustrated in FIGS. **1A** to **1D**, in the transistor **10** of one embodiment of the present invention, the conductive films **14** and **15** are connected to the side and top portions of the semiconductor film **12** in the impurity regions **12b** and **12c**, respectively. Therefore, as compared to the case where the conductive films **14** and **15** are connected to only the top portion of the semiconductor film **12**, areas where the conductive films **14** and **15** are respectively in contact with the impurity regions **12b** and **12c** can be large. Accordingly, contact resistance between the conductive films **14** and **15** and the impurity regions **12b** and **12c** can be reduced; as a result, the on-state current of the transistor **10** can be increased.

Structure Example 2 of Transistor

[0055] Next, FIGS. **2A** to **2D** illustrate a structure example of a transistor **10** included in a semiconductor device of one embodiment of the present invention, which is different from the structure example in FIGS. **1A** to **1D**. FIG. **2A** is a plan view of the transistor **10**. Note that to clarify the layout of the transistor **10**, a variety of insulating films are omitted in FIG. **2A**. FIG. **2B** shows a circuit symbol of the transistor **10** illustrated in FIG. **2A**. FIG. **2C** is a cross-sectional view taken along dashed line A1-A2 in the plan view in FIG. **2A**. FIG. **2D** is a cross-sectional view taken along dashed line B1-B2 in the plan view in FIG. **2A**.

[0056] The transistor **10** illustrated in FIGS. **2A**, **2C**, and **2D** includes a conductive film **20** that functions as a gate electrode (BG) denoted by a circuit symbol in FIG. **2B**, over the substrate **11** having an insulating surface. Furthermore, the transistor **10** includes an insulating film **21** that functions as a gate insulating film and covers the conductive film **20**. Moreover, the transistor **10** includes the semiconductor film **12** overlapping the conductive film **20** with the insulating film **21** positioned therebetween. The semiconductor film **12** includes the channel formation region **12a** and the impurity regions **12b** and **12c** between which the channel formation region **12a** is positioned. Furthermore, the transistor **10** includes the insulating film **13** that functions as a gate insulating film and covers side and top portions of the semiconductor film **12** in the channel formation region **12a**. In addition, the transistor **10** includes the conductive film **17** that functions as a gate electrode (FG) denoted by a circuit symbol in FIG. **2B**, and overlaps side and top portions of the semiconductor film **12** in the channel formation region **12a** with the insulating film **13** positioned therebetween. The conductive film **17** is connected to the conductive film **20** through opening portions **22** and **23** of the insulating film **13** and the insulating film **21**. Moreover, the transistor **10** includes the conductive films **14** and **15** that function as a source electrode (S) and a drain electrode (D) denoted by circuit symbols in FIG. **2B**, and are connected to side and top

portions of the semiconductor film **12** in the impurity regions **12b** and **12c**.

[0057] FIGS. 2A, 2C, and 2D illustrate an example in which the insulating film **16** is provided over the semiconductor film **12**, the insulating film **13**, and the conductive film **17**, and the conductive films **14** and **15** are provided over the insulating film **16**. Furthermore, in FIGS. 2A, 2C, and 2D, the conductive films **14** and **15** are connected to the impurity regions **12b** and **12c** through the opening portions **18** and **19** of the insulating film **16**, respectively.

[0058] FIGS. 2A, 2C, and 2D illustrate an example in which the opening portion **22** and the opening portion **23** face each other with the semiconductor film **12** positioned therebetween.

[0059] As illustrated in FIGS. 2A to 2D, in the transistor **10** of one embodiment of the present invention, the side and top portions of the semiconductor film **12** in the channel formation region **12a** and the conductive film **17** overlap each other, whereby carriers flow in a wide range including the side and top portions of the channel formation region **12a**. Therefore, an area on the substrate occupied by the channel formation region **12a** of the semiconductor film **12** can be reduced and the amount of carriers transferred in the transistor **10** can be increased. As a result, the on-state current of the transistor **10** is increased and the field-effect mobility of the transistor **10** is also increased. On the assumption that the length of the semiconductor film **12** in the channel formation region **12a** in the channel width direction (the channel width) is W , and the thickness of the semiconductor film **12** in the channel formation region **12a** is T , when the aspect ratio that corresponds to the ratio of the thickness T to the channel width W is high, a region where carrier flows becomes wider. Thus, the on-state current of the transistor **10** is further increased and the field-effect mobility of the transistor **10** is further increased.

[0060] As described above, in the case of the transistor **10** using the semiconductor film **12** that is a thin film, the aspect ratio is preferably such that the high crystallinity of the semiconductor film **12** can be ensured. In the case where the semiconductor film **12** contains silicon or the case where the semiconductor film **12** contains silicon and germanium, in consideration of ensuring the high crystallinity of the semiconductor film **12**, specifically, the thickness T is preferably greater than or equal to 5 nm and less than or equal to 150 nm, and further preferably greater than or equal to 20 nm and less than or equal to 100 nm. On the assumption that the thickness T falls within the above range, in consideration of the resolution of an exposure apparatus which is approximately several micrometers in the case of using a glass substrate, the specific aspect ratio is preferably greater than or equal to 0.05 and less than or equal to 10, and further preferably greater than or equal to 0.1 and less than or equal to 5, and still further preferably greater than or equal to 1 and less than or equal to 5.

[0061] Furthermore, as illustrated in FIGS. 2A to 2D, in the transistor **10** of one embodiment of the present invention, the conductive films **14** and **15** are connected to the side and top portions of the semiconductor film **12** in the impurity regions **12b** and **12c**, respectively. Therefore, as compared to the case where the conductive films **14** and **15** are connected to only the top portion of the semiconductor film **12**, areas where the conductive films **14** and **15** are respectively in contact with the impurity regions **12b** and **12c** can be large. Accordingly, contact resistance between the conductive films **14** and **15** and the impurity regions **12b** and **12c** can be reduced; as a result, the on-state current of the transistor **10** can be increased.

[0062] In the transistor **10** illustrated in FIGS. 2A to 2D, the conductive film **20** functioning as a gate electrode (BG) is provided in the vicinity of a surface of the semiconductor film **12** (on a back channel region side) which is far from the conductive film **17** functioning as a gate electrode (FG). The conductive film **20** is connected to the conductive film **17**. The above structure can prevent generation of fixed charge in the back channel region in the transistor **10** in FIGS. 2A to 2D, which can reduce the off-state current. Furthermore, in the transistor **10** in FIGS. 2A to 2D, since the conductive film **20** is connected to the conductive film **17**, the on-state current can be increased as compared to that in the transistor **10** in FIGS. 1A to 1D because a region in which carriers move extends over a large area.

[0063] Moreover, in the transistor **10** in FIGS. 2A to 2D, the conductive film **20** is provided below the semiconductor film **12** so as to be positioned below a channel formation region **12a**, and the conductive film **17** is provided over the semiconductor film **12** so as to overlap the channel formation region **12a**. Therefore, the semiconductor film **12** is supported from above and below by the conductive film **17** and the conductive film **20**; thus, the transistor **10** can have high strength against stress as compared to the transistor **10** in FIGS. 1A to 1D.

Structure Example 3 of Transistor

[0064] FIGS. 1 to 1D and FIGS. 2A to 2D illustrate an example of the transistor **10** in which the conductive film **14** and the conductive film **15** functioning as a source electrode and a drain electrode are provided over the insulating film **16**, and the conductive film **14** and the conductive film **15** are respectively connected to the impurity region **12b** and the impurity region **12c** through the opening portions of the insulating film **16**. The insulating film **16** may be provided over the conductive film **14** and the conductive film **15** in the transistor **10** of one embodiment of the present invention.

[0065] The structure of the transistor **10** illustrated in FIGS. 3A to 3D is different from that of the transistor **10** in FIGS. 1A to 1D in that the insulating film **16** is provided over the conductive film **14** and the conductive film **15**. FIG. 3A is a plan view of the transistor **10**. Note that to clarify the layout of the transistor **10**, a variety of insulating films are omitted in FIG. 3A. FIG. 3B shows a circuit symbol of the transistor **10** illustrated in FIG. 3A. FIG. 3C is a cross-sectional view taken along dashed line A1-A2 in the plan view in FIG. 3A. FIG. 3D is a cross-sectional view taken along dashed line B1-B2 in the plan view in FIG. 3A.

[0066] The transistor **10** illustrated in FIGS. 3A, 3C, and 3D includes the conductive film **14** and the conductive film **15** that function as a source electrode(S) and a drain electrode (D) denoted by circuit symbols in FIG. 3B and are connected to side and top portions of the semiconductor film **12** in the impurity region **12b** and the impurity region **12c**. In FIGS. 3A, 3C, and 3D, the insulating film **16** is provided over the semiconductor film **12**, the insulating film **13**, the conductive film **17**, the conductive film **14**, and the conductive film **15**.

[0067] The structure of the transistor **10** in FIGS. 4A to 4D is different from that of the transistor **10** in FIGS. 2A to 2D in that the insulating film **16** is provided over the conductive film **14** and the conductive film **15**. FIG. 4A is a plan view of the transistor **10**. Note that to clarify the layout of the transistor **10**, a variety of insulating films are omitted in FIG. 4A. FIG. 4B shows a circuit symbol of the transistor **10** illustrated in FIG. 4A. FIG. 4C is a cross-sectional view taken along dashed line A1-A2 in the plan view in FIG. 4A. FIG. 4D is a cross-sectional view taken along dashed line B1-B2 in the plan view in FIG. 4A.

[0068] The transistor **10** illustrated in FIGS. 4A, 4C, and 4D includes the conductive film **14** and the conductive film **15** that function as a source electrode(S) and a drain electrode (D) denoted by circuit symbols in FIG. 4B and are connected to side and top portions of the semiconductor film **12** in the impurity region **12b** and the impurity region **12c**. In FIGS. 4A, 4C, and 4D, the insulating film **16** is provided over the semiconductor film **12**, the insulating film **13**, the conductive film **17**, the conductive film **14**, and the conductive film **15**.

[0069] In a manner similar to that the transistors **10** in FIGS. 1A to 1D and FIGS. 2A to 2D, in the transistors **10** in FIGS. 3A to 3D and FIGS. 4 to 4D, the side and top portions of the semiconductor film **12** in the channel formation region **12a** and the conductive film **17** overlap each other, whereby carriers flow in a wide range including the side and top portions of the channel formation region **12a**. Therefore, an area on the substrate occupied by the channel formation region **12a** of the semiconductor film **12** can be reduced and the amount of carriers transferred in the transistor **10** can be increased. As a result, the on-state current of the transistor **10** is increased and the field-effect mobility of the transistor **10** is also increased. On the assumption that the length of the semiconductor film **12** in the channel formation region **12a** in the channel width direction (the channel width) is W , and the thickness of the semiconductor film **12** in the channel formation

region **12a** is T, when the aspect ratio that corresponds to the ratio of the thickness T to the channel width W is high, a region where carrier flows becomes wider. Thus, the on-state current of the transistor **10** is further increased and the field-effect mobility of the transistor **10** is further increased.

[0070] As described above, in the case of the transistor **10** using the semiconductor film **12** that is a thin film, the aspect ratio is preferably such that the high crystallinity of the semiconductor film **12** can be ensured. In the case where the semiconductor film **12** contains silicon or the case where the semiconductor film **12** contains silicon and germanium, in consideration of ensuring the high crystallinity of the semiconductor film **12**, specifically, the thickness T is preferably greater than or equal to 5 nm and less than or equal to 150 nm, and further preferably greater than or equal to 20 nm and less than or equal to 100 nm. On the assumption that the thickness T falls within the above range, in consideration of the resolution of an exposure apparatus which is approximately several micrometers in the case of using a glass substrate, the specific aspect ratio is preferably greater than or equal to 0.05 and less than or equal to 10, and further preferably greater than or equal to 0.1 and less than or equal to 5, and still further preferably greater than or equal to 1 and less than or equal to 5.

[0071] Furthermore, in a manner similar to that of the transistors **10** illustrated in FIGS. **1A** to **1D** and FIGS. **2A** to **2D**, also in the transistors **10** illustrated in FIGS. **3A** to **3D** and FIGS. **4A** to **4D**, the conductive films **14** and **15** are connected to the side and top portions of the semiconductor film **12** in the impurity regions **12b** and **12c**, respectively. Therefore, as compared to the case where the conductive films **14** and **15** are connected to only the top portion of the semiconductor film **12**, areas where the conductive films **14** and **15** are respectively in contact with the impurity regions **12b** and **12c** can be large. Accordingly, contact resistance between the conductive films **14** and **15** and the impurity regions **12b** and **12c** can be reduced; as a result, the on-state current of the transistor **10** can be increased.

[0072] Also in the transistor **10** illustrated in FIGS. **4A** to **4D**, the conductive film **20** functioning as a gate electrode (BG) is provided on the back channel region side. The conductive film **20** is connected to the conductive film **17**. The above structure can prevent generation of fixed charge in the back channel region in the transistor **10** in FIGS. **4A** to **4D**, which can reduce the off-state current. Furthermore, in the transistor **10** in FIGS. **4A** to **4D**, since the conductive film **20** is connected to the conductive film **17**, the on-state current can be increased as compared to that in the transistor **10** in FIGS. **1A** to **1D** because a region in which carriers move extends over a large area.

[0073] Moreover, in the transistor **10** in FIGS. **4A** to **4D**, the conductive film **20** is provided below the semiconductor film **12** so as to be positioned below the channel formation region **12a**, and the conductive film **17** is provided over the semiconductor film **12** so as to overlap the channel formation region **12a**. Therefore, the semiconductor film **12** is supported from above and below by the conductive film **17** and the conductive film **20**; thus, the transistor **10** can have high strength against stress as compared to the transistor **10** in FIGS. **1A** to **1D**.

Structure Example 4 of Transistor

[0074] The transistors **10** in FIGS. **2A** to **2D** and FIGS. **4A** to **4D** are each an example in which the conductive film **17** is connected to the conductive film **20**. In the transistor **10** of one embodiment of the present invention, the conductive film **17** may be electrically isolated from the conductive film **20**.

[0075] The transistor **10** illustrated in FIGS. **5A** to **5D** is different from the transistor **10** in FIGS. **2A** to **2D** in that the conductive film **17** is electrically isolated from the conductive film **20**. FIG. **5A** is a plan view of the transistor **10**. Note that to clarify the layout of the transistor **10**, a variety of insulating films are omitted in FIG. **5A**. FIG. **5B** shows a circuit symbol of the transistor **10** illustrated in FIG. **5A**. FIG. **5C** is a cross-sectional view taken along dashed line A1-A2 in the plan view in FIG. **5A**. FIG. **5D** is a cross-sectional view taken along dashed line B1-B2 in the plan view

in FIG. 5A.

[0076] The transistor **10** illustrated in FIGS. 5A, 5C, and 5D includes the conductive film **20** that functions as a gate electrode (BG) denoted by a circuit symbol in FIG. 5B. In addition, the transistor **10** includes the conductive film **17** that functions as a gate electrode (FG) denoted by a circuit symbol in FIG. 5B, and overlaps side and top portions of the semiconductor film **12** in the channel formation region **12a** with the insulating film **13** positioned therebetween. As illustrated in FIGS. 5A, 5C, and 5D, the conductive film **17** is electrically isolated from the conductive film **20**.

[0077] In a manner similar to that the transistors **10** in FIGS. 2A to 2D and FIGS. 4A to 4D, in the transistor **10** in FIGS. 5A to 5D, the side and top portions of the semiconductor film **12** in the channel formation region **12a** and the conductive film **17** overlap each other, whereby carriers flow in a wide range including the side and top portions of the channel formation region **12a**. Therefore, an area on the substrate occupied by the channel formation region **12a** of the semiconductor film **12** can be reduced and the amount of carriers transferred in the transistor **10** can be increased. As a result, the on-state current of the transistor **10** is increased and the field-effect mobility of the transistor **10** is also increased. On the assumption that the length of the semiconductor film **12** in the channel formation region **12a** in the channel width direction (the channel width) is W , and the thickness of the semiconductor film **12** in the channel formation region **12a** is T , when the aspect ratio that corresponds to the ratio of the thickness T to the channel width W is high, a region where carrier flows becomes wider. Thus, the on-state current of the transistor **10** is further increased and the field-effect mobility of the transistor **10** is further increased.

[0078] As described above, in the case of the transistor **10** using the semiconductor film **12** that is a thin film, the aspect ratio is preferably such that the high crystallinity of the semiconductor film **12** can be ensured. In the case where the semiconductor film **12** contains silicon or the case where the semiconductor film **12** contains silicon and germanium, in consideration of ensuring the high crystallinity of the semiconductor film **12**, specifically, the thickness T is preferably greater than or equal to 5 nm and less than or equal to 150 nm, and further preferably greater than or equal to 20 nm and less than or equal to 100 nm. On the assumption that the thickness T falls within the above range, in consideration of the resolution of an exposure apparatus which is approximately several micrometers in the case of using a glass substrate, the specific aspect ratio is preferably greater than or equal to 0.05 and less than or equal to 10, and further preferably greater than or equal to 0.1 and less than or equal to 5, and still further preferably greater than or equal to 1 and less than or equal to 5.

[0079] Furthermore, in a manner similar to that of the transistors **10** illustrated in FIGS. 2A to 2D and FIGS. 4A to 4D, also in the transistor **10** illustrated in FIGS. 5A to 5D, the conductive films **14** and **15** are connected to the side and top portions of the semiconductor film **12** in the impurity regions **12b** and **12c**, respectively. Therefore, as compared to the case where the conductive films **14** and **15** are connected to only the top portion of the semiconductor film **12**, areas where the conductive films **14** and **15** are respectively in contact with the impurity regions **12b** and **12c** can be large. Accordingly, contact resistance between the conductive films **14** and **15** and the impurity regions **12b** and **12c** can be reduced; as a result, the on-state current of the transistor **10** can be increased.

[0080] In the transistor **10** illustrated in FIGS. 5A to 5D, the conductive film **20** functioning as a gate electrode (BG) is provided on the back channel region side. Therefore, in the transistor **10** in FIGS. 5A to 5D, generation of fixed charge in the back channel region can be inhibited by supplying a predetermined potential to the conductive film **20**, which can reduce the off-state current. Furthermore, in the transistor **10** in FIGS. 5A to 5D, the threshold voltage of the transistor **10** can be controlled to a desired value by a potential supplied to the conductive film **17**.

[0081] Moreover, in the transistor **10** in FIGS. 5A to 5D, the conductive film **20** is provided below the semiconductor film **12** so as to be positioned below the channel formation region **12a**, and the conductive film **17** is provided over the semiconductor film **12** so as to overlap the channel

formation region **12a**. Therefore, the semiconductor film **12** is supported from above and below by the conductive film **17** and the conductive film **20**; thus, the transistor **10** can have high strength against stress as compared to the transistor **10** in FIGS. **1A** to **1D**.

[0082] FIGS. **5A** to **5D** illustrate a structure example of the transistor **10** in which the conductive film **14** and the conductive film **15** functioning as a source electrode and a drain electrode are provided over the insulating film **16**, and the conductive film **14** and the conductive film **15** are respectively connected to the impurity region **12b** and the impurity region **12c** through opening portions of the insulating film **16**, in a manner similar to that of the transistor **10** in FIGS. **2A** to **2D**. Note that in one embodiment of the present invention, the insulating film **16** may be provided over the conductive film **14** and the conductive film **15** in the transistor **10** in FIGS. **5A** to **5D**, in a manner similar to that in the transistor **10** in FIGS. **4A** to **4D**.

Structure Example 5 of Transistor

[0083] Next, FIGS. **6A** to **6D** illustrate a structure example of the transistor **10** in which a conductive film electrically connected to the conductive film **20** is provided in the same layer as the conductive film **17**. FIG. **6A** is a plan view of the transistor **10**. Note that to clarify the layout of the transistor **10**, a variety of insulating films are omitted in FIG. **6A**. FIG. **6B** shows a circuit symbol of the transistor **10** illustrated in FIG. **6A**. FIG. **6C** is a cross-sectional view taken along dashed line A1-A2 in the plan view in FIG. **6A**. FIG. **6D** is a cross-sectional view taken along dashed line B1-B2 in the plan view in FIG. **6A**.

[0084] The transistor **10** illustrated in FIGS. **6A**, **6C**, and **6D** includes the conductive film **20** that functions as a gate electrode (BG) denoted by a circuit symbol in FIG. **6B**, over the substrate **11** having an insulating surface. Furthermore, the transistor **10** includes the insulating film **21** that functions as a gate insulating film and covers the conductive film **20**. Moreover, the transistor **10** includes the semiconductor film **12** overlapping the conductive film **20** with the insulating film **21** positioned therebetween. The semiconductor film **12** includes the channel formation region **12a** and the impurity regions **12b** and **12c** between which the channel formation region **12a** is positioned. Furthermore, the transistor **10** includes the insulating film **13** that functions as a gate insulating film and covers side and top portions of the semiconductor film **12** in the channel formation region **12a**. In addition, the transistor **10** includes the conductive film **17** that functions as a gate electrode (FG) denoted by a circuit symbol in FIG. **6B**, and overlaps side and top portions of the semiconductor film **12** in the channel formation region **12a** with the insulating film **13** positioned therebetween. Moreover, the transistor **10** includes the conductive films **14** and **15** that function as a source electrode(S) and a drain electrode (D) denoted by circuit symbols in FIG. **6B**, and that are connected to side and top portions of the semiconductor film **12** in the impurity regions **12b** and **12c**, and includes a conductive film **24** connected to the conductive film **17**.

[0085] FIGS. **6A**, **6C**, and **6D** illustrate an example in which the insulating film **16** is provided over the semiconductor film **12**, the insulating film **13**, and the conductive film **17**, and the conductive films **14**, **15**, and **24** are provided over the insulating film **16**. In addition, the conductive film **14** and the conductive film **15** are connected to the impurity region **12b** and the impurity region **12c** through an opening portion **18** and an opening portion **19**, respectively, and the conductive film **24** is connected to the conductive film **17** through an opening portion **25** of the insulating film **16**.

[0086] In addition, in FIGS. **6A**, **6C**, and **6D**, an opening portion **28** and an opening portion **29** face each other with the semiconductor film **12** positioned therebetween.

[0087] Furthermore, in FIGS. **6A**, **6C**, and **6D**, a conductive film **26** and a conductive film **27** are provided in the same layer as the conductive film **17**, specifically, over the insulating film **13**. The conductive film **26** and the conductive film **27** are connected to the conductive film **20** through an opening portion **28** and an opening portion **29** of the insulating film **13** and the insulating film **21**.

[0088] As illustrated in FIGS. **6A** to **6D**, in the transistor **10** of one embodiment of the present invention, the side and top portions of the semiconductor film **12** in the channel formation region **12a** and the conductive film **17** overlap each other, whereby carriers flow in a wide range including

the side and top portions of the channel formation region **12a**. Therefore, an area on the substrate occupied by the channel formation region **12a** of the semiconductor film **12** can be reduced and the amount of carriers transferred in the transistor **10** can be increased. As a result, the on-state current of the transistor **10** is increased and the field-effect mobility of the transistor **10** is also increased. On the assumption that the length of the semiconductor film **12** in the channel formation region **12a** in the channel width direction (the channel width) is W , and the thickness of the semiconductor film **12** in the channel formation region **12a** is T , when the aspect ratio that corresponds to the ratio of the thickness T to the channel width W is high, a region where carrier flows becomes wider. Thus, the on-state current of the transistor **10** is further increased and the field-effect mobility of the transistor **10** is further increased.

[0089] As described above, in the case of the transistor **10** using the semiconductor film **12** that is a thin film, the aspect ratio is preferably such that the high crystallinity of the semiconductor film **12** can be ensured. In the case where the semiconductor film **12** contains silicon or the case where the semiconductor film **12** contains silicon and germanium, in consideration of ensuring the high crystallinity of the semiconductor film **12**, specifically, the thickness T is preferably greater than or equal to 5 nm and less than or equal to 150 nm, and further preferably greater than or equal to 20 nm and less than or equal to 100 nm. On the assumption that the thickness T falls within the above range, in consideration of the resolution of an exposure apparatus which is approximately several micrometers in the case of using a glass substrate, the specific aspect ratio is preferably greater than or equal to 0.05 and less than or equal to 10, and further preferably greater than or equal to 0.1 and less than or equal to 5, and still further preferably greater than or equal to 1 and less than or equal to 5.

[0090] Furthermore, as illustrated in FIGS. **6A** to **6D**, in the transistor **10** of one embodiment of the present invention, the conductive films **14** and **15** are connected to the side and top portions of the semiconductor film **12** in the impurity regions **12b** and **12c**, respectively. Therefore, as compared to the case where the conductive films **14** and **15** are connected to only the top portion of the semiconductor film **12**, areas where the conductive films **14** and **15** are respectively in contact with the impurity regions **12b** and **12c** can be large. Accordingly, contact resistance between the conductive films **14** and **15** and the impurity regions **12b** and **12c** can be reduced; as a result, the on-state current of the transistor **10** can be increased.

[0091] In the transistor **10** illustrated in FIGS. **6A** to **6D**, the conductive film **20** functioning as a gate electrode (BG) is provided on the back channel region side. Therefore, in the transistor **10** in FIGS. **6A** to **6D**, generation of fixed charge in the back channel region can be inhibited by supplying a predetermined potential to the conductive film **20** through the conductive film **26** or the conductive film **27** connected to the conductive film **20**, which can reduce the off-state current. Furthermore, in the transistor **10** in FIGS. **6A** to **6D**, the threshold voltage of the transistor **10** can be controlled to a desired value by a potential supplied to the conductive film **17**.

[0092] Moreover, in the transistor **10** in FIGS. **6A** to **6D**, the conductive film **20** is provided below the semiconductor film **12** so as to be positioned below the channel formation region **12a**, and the conductive film **17** is provided over the semiconductor film **12** so as to overlap the channel formation region **12a**. Therefore, the semiconductor film **12** is supported from above and below by the conductive film **17** and the conductive film **20**; thus, the transistor **10** can have high strength against stress as compared to the transistor **10** in FIGS. **1A** to **1D**.

Structure Example 6 of Transistor

[0093] The transistor **10** in FIGS. **2A** to **2D** illustrate the example in which the conductive film **17** is connected to the conductive film **20** through the opening portion **22** and the opening portion **23**, which face each other with the semiconductor film **12** positioned therebetween. In the transistor **10** of one embodiment of the present invention, the conductive film **17** may be connected to the conductive film **20** through an opening portion existing on one side of the semiconductor film **12**.

[0094] The transistor **10** in FIGS. **7A** to **7D** is different from the transistor **10** in FIGS. **2A** to **2D** in

that the conductive film **17** is connected to the conductive film **20** through the opening portion **22** existing on one side of the semiconductor film **12**. FIG. 7A is a plan view of the transistor **10**. Note that to clarify the layout of the transistor **10**, a variety of insulating films are omitted in FIG. 7A. FIG. 7B shows a circuit symbol of the transistor **10** illustrated in FIG. 7A. FIG. 7C is a cross-sectional view taken along dashed line A1-A2 in the plan view in FIG. 7A. FIG. 7D is a cross-sectional view taken along dashed line B1-B2 in the plan view in FIG. 7A.

[0095] Specifically, in the transistor **10** in FIGS. 7A, 7C, and 7D, the conductive film **17** functioning as a gate electrode (FG) denoted by a circuit symbol in FIG. 7B is connected to the conductive film **20** functioning as a gate electrode (BG) denoted by a circuit symbol in FIG. 7B, through the opening portion **22** of the insulating films **13** and **21**.

[0096] Note that FIGS. 7A to 7D illustrate the structure example of the transistor **10** in which the conductive film **14** and the conductive film **15** functioning as a source electrode and a drain electrode are provided over the insulating film **16**, and the conductive film **14** and the conductive film **15** are respectively connected to the impurity region **12b** and the impurity region **12c** through the opening portions of the insulating film **16**, in a manner similar to that of the transistor **10** illustrated in FIGS. 2A to 2D. Note that in one embodiment of the present invention, the insulating film **16** may be provided over the conductive film **14** and the conductive film **15** in the transistor **10** in FIGS. 7A to 7D, in a manner similar to that of the transistor **10** in FIGS. 4A to 4D.

[0097] In a manner similar to that the transistors **10** in FIGS. 1A to 1D and FIGS. 2A to 2D, in the transistor **10** in FIGS. 7A to 7D, the side and top portions of the semiconductor film **12** in the channel formation region **12a** and the conductive film **17** overlap each other, whereby carriers flow in a wide range including the side and top portions of the channel formation region **12a**. Therefore, an area on the substrate occupied by the channel formation region **12a** of the semiconductor film **12** can be reduced and the amount of carriers transferred in the transistor **10** can be increased. As a result, the on-state current of the transistor **10** is increased and the field-effect mobility of the transistor **10** is also increased. On the assumption that the length of the semiconductor film **12** in the channel formation region **12a** in the channel width direction (the channel width) is W , and the thickness of the semiconductor film **12** in the channel formation region **12a** is T , when the aspect ratio that corresponds to the ratio of the thickness T to the channel width W is high, a region where carrier flows becomes wider. Thus, the on-state current of the transistor **10** is further increased and the field-effect mobility of the transistor **10** is further increased.

[0098] As described above, in the case of the transistor **10** using the semiconductor film **12** that is a thin film, the aspect ratio is preferably such that the high crystallinity of the semiconductor film **12** can be ensured. In the case where the semiconductor film **12** contains silicon or the case where the semiconductor film **12** contains silicon and germanium, in consideration of ensuring the high crystallinity of the semiconductor film **12**, specifically, the thickness T is preferably greater than or equal to 5 nm and less than or equal to 150 nm, and further preferably greater than or equal to 20 nm and less than or equal to 100 nm. On the assumption that the thickness T falls within the above range, in consideration of the resolution of an exposure apparatus which is approximately several micrometers in the case of using a glass substrate, the specific aspect ratio is preferably greater than or equal to 0.05 and less than or equal to 10, and further preferably greater than or equal to 0.1 and less than or equal to 5, and still further preferably greater than or equal to 1 and less than or equal to 5.

[0099] Furthermore, in a manner similar to that of the transistors **10** illustrated in FIGS. 1A to 1D and FIGS. 2A to 2D, also in the transistor **10** illustrated in FIGS. 7A to 7D, the conductive films **14** and **15** are connected to the side and top portions of the semiconductor film **12** in the impurity regions **12b** and **12c**, respectively. Therefore, as compared to the case where the conductive films **14** and **15** are connected to only the top portion of the semiconductor film **12**, areas where the conductive films **14** and **15** are respectively in contact with the impurity regions **12b** and **12c** can be large. Accordingly, contact resistance between the conductive films **14** and **15** and the impurity

regions **12b** and **12c** can be reduced; as a result, the on-state current of the transistor **10** can be increased.

[0100] In a manner similar to that of the transistor **10** in FIGS. **2A** to **2D**, also in the transistor **10** illustrated in FIGS. **7A** to **7D**, the conductive film **20** functioning as a gate electrode (BG) is provided on the back channel region side. The conductive film **20** is connected to the conductive film **17**. The above structure can prevent generation of fixed charge in the back channel region in the transistor **10** in FIGS. **7A** to **7D**, which can reduce the off-state current. Furthermore, in the transistor **10** in FIGS. **7A** to **7D**, since the conductive film **20** is connected to the conductive film **17**, the on-state current can be increased as compared to that in the transistor **10** in FIGS. **1A** to **1D** because a region in which carriers move extends over a large area.

[0101] Moreover, in the transistor **10** in FIGS. **7A** to **7D**, the conductive film **20** is provided below the semiconductor film **12** so as to be positioned below the channel formation region **12a**, and the conductive film **17** is provided over the semiconductor film **12** so as to overlap the channel formation region **12a**. Therefore, the semiconductor film **12** is supported from above and below by the conductive film **17** and the conductive film **20**; thus, the transistor **10** can have high strength against stress as compared to the transistor **10** in FIGS. **1A** to **1D**.

[0102] Note that a variety of semiconductor elements may be provided between the substrate **11** and the transistor **10** in any of FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D**. In this case, the transistor **10** may be provided over an insulating film covering the semiconductor elements.

[0103] In the transistor **10** in any of FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D**, a state where the conductive films **14** and **15** are connected to the impurity regions **12b** and **12c** does not mean only a state where the conductive films **14** and **15** are in direct contact with the impurity regions **12b** and **12c**. For example, the connected state includes a state where an insulating film such as a native oxide film that has a thickness small enough to keep electrical connection is provided between the conductive films **14** and **15** and the impurity regions **12b** and **12c**.

[0104] In the transistor **10** in any of FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D**, in addition to the channel formation region **12a**, the impurity region **12b**, and the impurity region **12c**, the semiconductor film **12** may include a lightly doped drain (LDD) region which has a lower concentration of an impurity imparting one conductivity type to a semiconductor than the impurity regions **12b** and **12c**. The LDD region can be provided between the channel formation region **12a** and the impurity region **12b** or between the impurity region **12c** and the channel formation region **12a**.

[0105] The transistor **10** in any of FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** is an example in which an end portion of the conductive film **17** overlaps a boundary between the channel formation region **12a** and each of the impurity regions **12b** and **12c** in a cross-sectional view in the channel length direction, i.e., a cross-sectional view taken along dashed line A1-A2. Note that in one embodiment of the present invention, the conductive film **17** may overlap the boundary between the channel formation region **12a** and the impurity region **12b** or the boundary between the channel formation region **12a** and the impurity region **12c**. In this case, the conductive film **17** overlaps part of the impurity region **12b** or part of the impurity region **12c** with the insulating film **13** positioned therebetween. Alternatively, the end portions of the conductive film **17** may overlap the channel formation region **12a** in one embodiment of the present invention. In this case, the conductive film **17** does not overlap part of the channel formation region **12a** with the insulating film **13** positioned therebetween.

Alternatively, in the case where the LDD region is provided in the semiconductor film **12**, the conductive film **17** may overlap part of the LDD region with the insulating film **13** positioned therebetween.

Structure Example 7 of Transistor

[0106] FIG. 8 is an example of a plan view illustrating a plurality of transistors **10** connected in series. Each of the plurality of transistors **10** corresponds to the transistor **10** illustrated in FIGS. 2A to 2D.

[0107] Note that in this specification, a state in which transistors are connected to each other in series means, for example, a state in which only one of a source and a drain of a first transistor is connected to only one of a source and a drain of a second transistor. In addition, a state in which transistors are connected in parallel means a state in which one of a source and a drain of a first transistor is connected to one of a source and a drain of a second transistor and the other of the source and the drain of the first transistor is connected to the other of the source and the drain of the second transistor.

[0108] Specifically, FIG. 8 illustrates a state where three transistors **10**, which are referred to as transistors **10a** to **10c**, are connected in series. Note that to clarify the layout of the transistors **10**, the insulating films are omitted in FIG. 8.

[0109] The transistors **10a** to **10c** share the semiconductor film **12**. The transistor **10a** includes a conductive film **30** and a conductive film **31** that function as a source electrode and a drain electrode. The transistor **10b** includes the conductive film **31** and a conductive film **32** that function as a source electrode and a drain electrode. The transistor **10c** includes the conductive film **32** and a conductive film **33** that function as a source electrode and a drain electrode. Note that each of the conductive films **30** to **33** corresponds to one of the conductive film **14** and the conductive film **15** included in the transistor **10** in FIGS. 2A to 2D.

[0110] A conductive film **17a** functioning as a gate electrode of the transistor **10a** is connected to the conductive film **20** functioning as a gate electrode (BG), through an opening portion **18a** and an opening portion **19a**. A conductive film **17b** functioning as a gate electrode of the transistor **10b** is connected to the conductive film **20** functioning as a gate electrode (BG), through an opening portion **18b** and an opening portion **19b**. A conductive film **17c** functioning as a gate electrode of the transistor **10c** is connected to the conductive film **20** functioning as a gate electrode (BG), through an opening portion **18c** and an opening portion **19c**.

[0111] FIG. 9 illustrates a perspective view of the transistors **10a** to **10c** in FIG. 8. Note that to clarify the shapes of the transistors **10a** to **10c**, among insulating films functioning as gate insulating films, insulating films provided between the conductive films **17a** to **17c** and the semiconductor film **12** are referred to as insulating films **13a** to **13c**, and the insulating films other than the insulating films **13a** to **13c** are omitted in FIG. 9. Furthermore, the conductive films **30** to **33** are omitted in FIG. 9.

[0112] FIG. 8 and FIG. 9 illustrate an example in which all the conductive films **17a** to **17c**, which are respectively included in the transistors **10a** to **10c** connected in series, are connected to the conductive film **20**; however, the conductive films **17a** to **17c** may be connected to a plurality of conductive films **20** that are electrically isolated from each other.

Manufacturing Method

[0113] A specific method for manufacturing the transistor **10** is described with reference to FIGS. 10A and 10B, FIGS. 11A and 11B, FIGS. 12A and 12B, and FIGS. 13A and 13B, using, as examples, a transistor **10N** which has the same structure as the transistor **10** in FIGS. 2A to 2D and is an n-channel transistor, and a transistor **10P** which has the same structure as the transistor **10** in FIGS. 2A to 2D and is a p-channel transistor. Note that in FIGS. 10A and 10B, FIGS. 11A and 11B, FIGS. 12A and 12B, and FIGS. 13A and 13B, a cross section of a region where the transistor **10P** is formed in the channel length direction corresponds a cross-sectional view along dashed line C1-C2. A cross section of a region where the transistor **10N** is formed in the channel length direction corresponds to a cross-sectional view along dashed line C3-C4, and a cross section in the channel width direction corresponds a cross-sectional view along dashed line C5-C6.

[0114] First, as illustrated in FIG. 10A, an insulating film **301** is formed over a substrate **300** which has heat resistance, and then a conductive film **302** and a conductive film **303** each functioning as a

gate electrode (BG) are formed over the insulating film **301**.

[0115] As the substrate **300**, a substrate having heat resistance high enough to withstand a later manufacturing step is preferable, and for example, a glass substrate, a quartz substrate, a ceramic substrate, a sapphire substrate, or the like is used.

[0116] The insulating film **301** has a function of preventing adverse effects on the electrical characteristics of the transistor **10P** and the transistor **10N** by inhibiting alkali metal and alkaline earth metal included in the substrate **300** from diffusing into a semiconductor film **306** and a semiconductor film **307**, which are formed later. The insulating film **301** is formed using an insulating material such as silicon oxide, silicon nitride, silicon oxynitride, or silicon nitride oxide, by a CVD method, a sputtering method, or the like.

[0117] Each of the conductive films **302** and **303** may be formed using a single layer or a stacked layer of a conductive film containing one or more kinds selected from aluminum, titanium, chromium, cobalt, nickel, copper, yttrium, zirconium, molybdenum, ruthenium, silver, tantalum, and tungsten. For example, the conductive films **302** and **303** may be a conductive film in which a copper film is stacked over a tungsten nitride film or a single-layer tungsten film. In this embodiment, a 200-nm-thick tungsten film is used as the conductive films **302** and **303**.

[0118] Next, as illustrated in FIG. **10B**, an insulating film **304** is formed over the conductive film **302** and the conductive film **303**, and a semiconductor film **305** is formed over the insulating film **304**.

[0119] The insulating film **304** can be formed using a single layer or stacked layer of silicon nitride, silicon oxide, silicon nitride oxide, or silicon oxynitride, by a plasma CVD method, a sputtering method, or the like. In the case of using a stacked layer, for example, three-layer structure which is formed by stacking a silicon oxide film, a silicon nitride film and a silicon oxide film in this order from the side of the substrate **300** is preferable.

[0120] It is preferable that, after forming the insulating film **304**, the semiconductor film **305** be formed without being exposed to the air. The thickness of the semiconductor film **305** is preferably greater than or equal to 5 nm and less than or equal to 150 nm, further preferably greater than or equal to 20 nm and less than or equal to 100 nm. The semiconductor film **305** may be any of an amorphous semiconductor and a polycrystalline semiconductor. Not only silicon but also silicon germanium can be used as the semiconductor. When silicon germanium is used, it is preferable that the concentration of germanium be approximately 0.01 atomic % or more and 4.5 atomic % or less.

[0121] The semiconductor film **305** may be crystallized by any of a variety of techniques.

Examples of the various techniques of crystallization are a laser crystallization method using a laser beam and a crystallization method using a catalytic element. Alternatively, a crystallization method using a catalytic element and a laser crystallization method may be combined. In the case where a substrate superior in heat resistance, such as a quartz substrate, is used as the substrate **300**, it is possible to combine any of the following crystallization methods: a thermal crystallization method which uses an electrically-heated furnace; a lump anneal crystallization method which uses infrared light; a crystallization method which uses a catalytic element; and high-temperature annealing at approximately 950° C. may be used.

[0122] Note that the semiconductor film **305** may be subjected to channel doping, in which an impurity element which imparts p-type conductivity or an impurity element which imparts n-type conductivity is added at a low concentration. As the p-type impurity element, boron (B), aluminum (Al), gallium (Ga), or the like can be used. As the impurity element imparting n-type conductivity, phosphorus (P), arsenic (As), or the like can be used. For example, in the case where boron (B) is used as an impurity element, channel doping is performed so that boron is contained in the semiconductor film **305** at a concentration higher than or equal to 1×10^{16} atoms/cm³ and lower than or equal to 5×10^{17} atoms/cm³.

[0123] Next, as illustrated in FIG. **11A**, the semiconductor film **305** is processed by etching or the like to form the island-shaped semiconductor films **306** and **307** over the insulating film **304**. The

semiconductor film **306** overlaps the conductive film **302** with the insulating film **304** positioned therebetween, and the semiconductor film **307** overlaps the conductive film **303** with the insulating film **304** positioned therebetween.

[0124] Subsequently, as illustrated in FIG. **11B**, an insulating film **308** is formed to cover the semiconductor film **306** and the semiconductor film **307**. The insulating film **308** may be formed using a single layer or a stacked layer of silicon nitride, silicon oxide, silicon nitride oxide, or/and silicon oxynitride by a plasma CVD method, a sputtering method, or the like. In the case of using a stacked layer, for example, a three-layer structure which is formed by stacking a silicon oxide film, a silicon nitride film and a silicon oxide film in this order from the side of the substrate **300** is preferable.

[0125] The insulating film **308** may be formed by oxidizing or nitriding the surfaces of the semiconductor films **306** and **307** by performing a high-density plasma treatment. High-density plasma treatment is performed by using, for example, a mixed gas of a rare gas such as He, Ar, Kr, or Xe; and oxygen, nitrogen oxide, ammonia, nitrogen, or hydrogen. In this case, when excitation of a plasma is performed by introducing a microwave, a plasma with a low electron temperature and a high density can be generated. The surfaces of the semiconductor films are oxidized or nitrided by an oxygen radical (there is a case where an OH radical is included) or a nitrogen radical (there is a case where an NH radical is included) generated by such high-density plasma, so that an insulating film with a thickness of greater than or equal to 1 nm and less than or equal to 20 nm, typically greater than or equal to 5 nm and less than or equal to 10 nm, is formed so as to be in contact with the semiconductor films. This insulating film with a thickness of greater than or equal to 5 nm and less than or equal to 10 nm is used as the insulating film **308**.

[0126] Since oxidation or nitridation of the semiconductor film by the above-described high-density plasma treatment is progressed with solid reaction, interface state density between the gate insulating film and the semiconductor film can be extremely lowered. In addition, the semiconductor films are directly oxidized or nitrided by the high-density plasma treatment, so that variation in thickness of the insulating film to be formed can be suppressed. In the case where the semiconductor films have crystallinity, by oxidizing surfaces of the semiconductor films under a solid-phase reaction by the high-density plasma treatment, rapid oxidation can be prevented only in a crystal grain boundary; thus, a gate insulating film with good uniformity and low interface state density can be formed. When the insulating film formed by the high-density plasma treatment is included in part or all of a gate insulating film of transistors, variations in characteristics of the transistors can be suppressed.

[0127] Next, as illustrated in FIG. **12A**, a conductive film is formed over the insulating film **308** and then the conductive film is processed (patterned) to have a predetermined shape, so that conductive films **309** and **310** are formed over the island-shaped semiconductor films **306** and **307**. Each of the conductive films **309** and **310** may be formed using a single layer or a stacked layer of a conductive film containing one or more kinds selected from aluminum, titanium, chromium, cobalt, nickel, copper, yttrium, zirconium, molybdenum, ruthenium, silver, tantalum, and tungsten. The conductive films **309** and **310** can be formed by a CVD method, a sputtering method, or the like.

[0128] Next, as illustrated in FIG. **12B**, a resist **311** is formed to cover the semiconductor film **306**, and an impurity element imparting n-type conductivity (typically P or As) is added to the semiconductor film **307** using the resist **311** and the conductive film **310** as masks. The addition of the impurity element can be performed by an ion implantation method at an accelerating voltage of greater than or equal to 60 keV and less than or equal to 100 keV so that the impurity concentration of the semiconductor film **307** is higher than or equal to 1×10^{19} atoms/cm³ and lower than or equal to 1×10^{20} atoms/cm³, for example. By the addition of the impurity, a pair of impurity regions **312** is formed in the semiconductor film **307**.

[0129] Then, as illustrated in FIG. **13A**, a resist **313** is formed to cover the semiconductor film **307**,

and an impurity element imparting p-type conductivity (typically B) is added to the semiconductor film **306** using the resist **313** and the conductive film **309** as masks. The addition of the impurity element can be performed by an ion implantation method at an accelerating voltage of greater than or equal to 20 keV and less than or equal to 40 keV so that the impurity concentration of the semiconductor film **306** is higher than or equal to 1×10^{19} atoms/cm³ and lower than or equal to 1×10^{20} atoms/cm³, for example. By the addition of the impurity, a pair of impurity regions **314** is formed in the semiconductor film **306**.

[0130] Next, as illustrated in FIG. **13B**, an insulating film **320** is formed to cover the substrate **300**, opening portions are formed in the insulating film **320**, and conductive films **321** which are in contact with the impurity regions **312** through the opening portions and conductive films **322** which are in contact with the impurity regions **314** through the opening portions are formed.

[0131] The insulating film **320** is formed by a plasma CVD method, a sputtering method, or the like using a single layer or a stacked layer of any of the following films: a silicon film; a silicon oxide film; a silicon oxynitride film; a silicon nitride oxide film; and a film containing an organic material such as an organic resin with high planarity. In this embodiment, a 100-nm-thick silicon oxide film is formed by a plasma CVD method.

[0132] Each of the conductive films **321** and **322** may be formed using a single layer or a stacked layer of a conductive film containing one or more kinds selected from aluminum, titanium, chromium, cobalt, nickel, copper, yttrium, zirconium, molybdenum, ruthenium, silver, tantalum, and tungsten.

[0133] Then, the impurity regions may be activated by heat treatment. For example, the activation can be performed by heat treatment in a nitrogen atmosphere at 550° C. for four hours.

[0134] Alternatively, after a silicon nitride film containing hydrogen is formed to a thickness of 100 nm, heat treatment may be performed in a nitrogen atmosphere at 410° C. for one hour to hydrogenate the semiconductor films **306** and **307**. Further alternatively, heat treatment may be performed in an atmosphere containing hydrogen at a temperature of 300° C. to 450° C. for 1 to 12 hours to hydrogenate the semiconductor films **306** and **307**. The thermal treatment can be performed by a thermal annealing method, a laser annealing method, an RTA method, or the like. Through the heat treatment, not only hydrogenation, but also activation of the impurity element added to the semiconductor films can be performed. As another means for the hydrogenation, plasma hydrogenation (using hydrogen that is excited by plasma) may be performed. In the hydrogenation process, a dangling bond can be terminated by using the thermally excited hydrogen.

[0135] Through the above series of processes, the p-channel transistor **10P** and the n-channel transistor **10N** are formed.

[0136] Note that the transistor **10P** and the transistor **10N** formed by the above method may be transferred onto a flexible substrate such as a plastic substrate which is separately prepared. The semiconductor elements can be transferred to another substrate by a variety of methods. Examples of the transfer method include a method in which a metal oxide film is provided between the substrate and the semiconductor element, and the metal oxide film is embrittled by crystallization so that the semiconductor element is separated off and transferred; a method in which an amorphous silicon film containing hydrogen is provided between the substrate and the semiconductor element, and the amorphous silicon film is removed by laser beam irradiation or etching so that the semiconductor element is separated off the substrate and transferred; a method in which the substrate, for which the semiconductor element is provided, is removed by mechanical cutting or etching with a solution or a gas so that the semiconductor element is cut off the substrate and transferred; and the like.

[0137] In this case, polyester typified by polyethylene terephthalate (PET), polyether sulfone (PES), polyethylene naphthalate (PEN), polycarbonate (PC), nylon, polyether etherketone (PEEK), polysulfone (PSF), polyether imide (PEI), polyarylate (PAR), polybutylene terephthalate (PBT),

polyimide, an acrylonitrile-butadiene-styrene resin, polyvinyl chloride, polypropylene, polyvinyl acetate, an acrylic resin, or the like can be given as examples of the material of the plastic substrate.

<Structure Example of Semiconductor Display Device>

[0138] Next, a structure example of a semiconductor display device which corresponds to one mode of a semiconductor device of the present invention is described.

[0139] In a semiconductor display device **70** illustrated in FIG. **14A**, a pixel portion **71** includes a plurality of pixels **55**, wirings GL (wirings GL**1** to GLy; y is a natural number) for selecting the pixels **55** row by a row, and wirings SL (wirings SL**1** to SLx; x is a natural number) for supplying image signals to the selected pixels **55**. Supply of signals to the wirings GL is controlled by a scan line driver circuit **72**. The supply of image signals to the wirings SL is controlled by a signal line driver circuit **73**. Each of the plurality of pixels **55** is connected to at least one of the wirings GL and at least one of the wirings SL.

[0140] Note that the kinds and number of the wirings in the pixel portion **71** can be determined by the structure, number, and position of the pixels **55**. Specifically, in the pixel portion **71** illustrated in FIG. **14A**, the pixels **55** are arranged in a matrix of x columns and y rows, and the wirings SL**1** to SLx and the wirings GL**1** to GLy are provided in the pixel portion **71** as an example.

[0141] Although FIG. **14A** illustrates the case where the scan line driver circuits **72**, the signal line driver circuit **73**, and the pixel portion **71** are formed over one substrate as an example, part or the whole of the signal line driver circuits **73** may be formed over a substrate different from a substrate over which the pixel portion **71** is formed. The transistors **10** illustrated in FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** can be used for any of the scan line driver circuit **72**, the signal line driver circuit **73**, and the pixel portion **71**.

[0142] FIG. **14B** illustrates a configuration example of the pixel **55**. Each of the pixels **55** includes a liquid crystal element **60**, a transistor **56** that controls the supply of an image signal to the liquid crystal element **60**, and a capacitor **57** that holds voltage between a pixel electrode and a common electrode of the liquid crystal element **60**. The liquid crystal element **60** includes the pixel electrode, the common electrode, and a liquid crystal layer containing a liquid crystal material to which voltage between the pixel electrode and the common electrode is applied.

[0143] The transistor **56** controls whether to supply the potential of the wiring SL to the pixel electrode of the liquid crystal element **60**. A predetermined potential is applied to the common electrode of the liquid crystal element **60**.

[0144] Connection between the transistor **56** and the liquid crystal element **60** is specifically described below. In FIG. **14B**, a gate of the transistor **56** is connected to any one of the wirings GL**1** to GLy. One of a source and a drain of the transistor **56** is connected to any one of the wirings SL**1** to SLx, and the other is connected to the pixel electrode of the liquid crystal element **60**.

[0145] The transmittance of the liquid crystal element **60** changes when the alignment of liquid crystal molecules included in the liquid crystal layer changes in accordance with the level of voltage applied between the pixel electrode and the common electrode. Accordingly, when the transmittance of the liquid crystal element **60** is controlled by the potential of an image signal supplied to the pixel electrode, gray-scale images can be displayed. In each of the plurality of pixels **55** included in the pixel portion **71**, the gray level of the liquid crystal element **60** is adjusted in response to an image signal containing image data; thus, an image is displayed on the pixel portion **71**.

[0146] FIG. **14B** illustrates an example in which one transistor **56** is used as a switch for controlling the supply of an image signal to the pixel **55**. However, a plurality of transistors functioning as one switch may be used in the pixel **55**.

[0147] The on-state current of any of the transistors **10** in FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** can be large. Therefore, the use of any of the transistors **10** in FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**,

FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D as the transistor 56 enables high speed supply of an image signal to the pixel 55, which can increase the image quality of the pixel 55. Furthermore, the off-state current of any of the transistors 10 in FIGS. 2A to 2D, FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D can be small. Therefore, the use of any of the transistors 10 in FIGS. 2A to 2D and FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D as the transistor 56 prevents charge from leaking through the transistor 56, which makes it possible to more certainly keep the potential of an image signal that has been supplied to the liquid crystal element 60 and the capacitor 57. As a result, a change in the transmittance of the liquid crystal element 60 due to leakage of charge within one frame period can be inhibited, whereby the quality of a displayed image can be improved.

[0148] Next, FIG. 14C illustrates another example of the pixel 55. The pixel 55 includes a transistor 95 for controlling supply of an image signal to the pixel 55, a light-emitting element 98, a transistor 96 for controlling the value of current supplied to the light-emitting element 98 in response to an image signal, and a capacitor 97 for holding the potential of an image signal.

[0149] Examples of the light-emitting element 98 include an element whose luminance is controlled by current or voltage, such as a light-emitting diode (LED) or an organic light-emitting diode (OLED). For example, an OLED includes at least an EL layer, an anode, and a cathode. The EL layer is formed using a single layer or a plurality of layers between the anode and the cathode, at least one of which is a light-emitting layer containing a light-emitting substance.

[0150] From the EL layer, electroluminescence is obtained by current supplied when a potential difference between the cathode and the anode is higher than or equal to the threshold voltage of the light-emitting element 98. As electroluminescence, there are luminescence (fluorescence) at the time of returning from a singlet-excited state to a ground state and luminescence (phosphorescence) at the time of returning from a triplet-excited state to a ground state.

[0151] The potential of one of the anode and the cathode of the light-emitting element 98 is controlled in response to an image signal supplied to the pixel 55. The one of the anode and the cathode whose potential is controlled in response to an image signal is used as a pixel electrode, and the other is used as a common electrode. A predetermined potential is applied to the common electrode of the light-emitting element 98, and the luminance of the light-emitting element 98 is determined by a potential difference between the pixel electrode and the common electrode. Thus, the luminance of the light-emitting element 98 is controlled by the potential of the image signal, so that the light-emitting element 98 can express gray level. In each of the plurality of pixels 55 included in the pixel portion, the gray level of the light-emitting element 98 is adjusted in response to an image signal containing image data; thus, an image is displayed on the pixel portion 71.

[0152] Next, connection among the transistor 95, the transistor 96, the capacitor 97, and the light-emitting element 98 which are included in the pixel 55 is described.

[0153] One of a source and a drain of the transistor 95 is connected to the wiring SL, and the other is connected to a gate of the transistor 96. A gate of the transistor 95 is connected to the wiring GL. One of a source and a drain of the transistor 96 is connected to a power supply line VL, and the other is connected to the light-emitting element 98. Specifically, the other of the source and the drain of the transistor 96 is connected to any one of the anode and the cathode of the light-emitting element 98. A predetermined potential is applied to the other of the anode and the cathode of the light-emitting element 98.

[0154] The on-state current of any of the transistors 10 in FIGS. 1A to 1D, FIGS. 2A to 2D, FIGS. 3A to 3D, FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D can be large. Therefore, the use of any of the transistors 10 in FIGS. 1A to 1D, FIGS. 2A to 2D, FIGS. 3A to 3D, FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D, as the transistor 95, enables high speed supply of an image signal to the pixel 55, which can increase the image quality of the pixel 55. Furthermore, the off-state current of any of the transistors 10 in FIGS. 2A to 2D, FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D can be small. Therefore, the

use of any of the transistors **10** in FIGS. **2A** to **2D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D**, as the transistor **95**, prevents charge from leaking through the transistor **95**, which makes it possible to more certainly keep the potential of an image signal that has been supplied to the capacitor **97**. As a result, a change in the luminance of the light-emitting element **98** due to leakage of charge within one frame period can be inhibited, whereby the quality of a displayed image can be improved.

[0155] For example, in this specification and the like, a display element, a display device which is a device including a display element, a light-emitting element, and a light-emitting device which is a device including a light-emitting element can employ various modes and can include various elements. Examples of a display element, a display device, a light-emitting element, or a light-emitting device include an EL (electroluminescent) element (e.g., an EL element including organic and inorganic materials, an organic EL element, or an inorganic EL element), an LED (e.g., a white LED, a red LED, a green LED, or a blue LED), a transistor (a transistor which emits light depending on current), an electron emitter, a liquid crystal element, electronic ink, an electrophoretic element, an electrowetting element, a grating light valve (GLV), a plasma display panel (PDP), a display device using a micro electro mechanical system (MEMS), a digital micromirror device (DMD), a digital micro shutter (DMS), an interferometric modulator display (IMOD), a electrowetting element, a piezoelectric ceramic display, and a carbon nanotube, which are display media whose contrast, luminance, reflectivity, transmittance, or the like is changed by electromagnetic action. Note that examples of display devices having EL elements include an EL display. Examples of display devices including electron emitters are a field emission display (FED) and an SED-type flat panel display (SED: surface-conduction electron-emitter display). Examples of display devices including liquid crystal elements include a liquid crystal display (e.g., a transmissive liquid crystal display, a transflective liquid crystal display, a reflective liquid crystal display, a direct-view liquid crystal display, or a projection liquid crystal display). An example of a display device including electronic ink or electrophoretic elements is electronic paper.

<Structure of Pixel>

[0156] Next, description is given of a structure example of the pixel **55** in a light-emitting device which is an example of the semiconductor display device **70** illustrated in FIG. **14A**. FIG. **15** is an example of a top view of the pixel **55** in FIG. **14C**. To clarify the layout of the pixel **55**, the insulating films and the light-emitting element **98** are omitted in FIG. **15**.

[0157] The pixel **55** in FIG. **15** includes the transistor **95**, the transistor **96**, and the capacitor **97**. FIG. **15** shows an example in which the transistor **95** and the transistor **96** which have the same structure as the transistor **10** in FIGS. **1A** to **1D** are used in the light-emitting device; however, in one embodiment of the present invention, any of the transistors **10** in FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** can be used for the light-emitting device.

[0158] The transistor **95** includes a conductive film **501** that functions as a gate electrode, a semiconductor film **502**, and a conductive film **503** that is connected to the semiconductor film **502** and functions as a source electrode or a drain electrode. The conductive film **501** functions as the wiring GL illustrated in FIG. **14C**. The conductive film **503** serves as the wiring SL illustrated in FIG. **14C**.

[0159] The capacitor **97** includes the semiconductor film **502**, a conductive film **504**, and an insulating film (not illustrated) provided between the semiconductor film **502** and the conductive film **504**. The conductive film **504** is connected to a conductive film **505** positioned in the same layer as the conductive film **503**.

[0160] The transistor **96** includes a conductive film **506** that functions as a gate electrode, a semiconductor film **507**, and a conductive film **508** and a conductive film **509** that are connected to the semiconductor film **507** and function as a source electrode and a drain electrode. Furthermore, the conductive film **509** is connected to a pixel electrode of the light-emitting element **98** in FIG.

14C. The conductive film **506** is connected to the semiconductor film **502** through a conductive film **510**. The conductive film **508** is connected to a conductive film **511**. The conductive film **511** functions as the wiring VL in FIG. **14C**.

[0161] For the electrode serving as the anode or the cathode, any of metals, alloys, electrically conductive compounds, and mixtures thereof can be used, for example. Specifically, indium oxide-tin oxide (ITO: indium tin oxide), indium oxide-tin oxide containing silicon or silicon oxide, indium oxide-zinc oxide (indium zinc oxide), indium oxide containing tungsten oxide and zinc oxide, gold (Au), platinum (Pt), nickel (Ni), tungsten (W), chromium (Cr), molybdenum (Mo), iron (Fe), cobalt (Co), copper (Cu), palladium (Pd), and titanium (Ti) can be used. In addition, an element belonging to Group 1 or Group 2 of the periodic table, for example, an alkali metal such as lithium (Li) or cesium (Cs), an alkaline earth metal such as calcium (Ca) or strontium (Sr), magnesium (Mg), an alloy containing such an element (MgAg, AlLi), a rare earth metal such as europium (Eu) or ytterbium (Yb), an alloy containing such an element, graphene, and the like can be used. The electrode is formed using a material selected from the above as appropriate and formed to an optimum thickness, so that a top-emission structure, a bottom-emission structure, or a dual-emission structure can be selectively formed.

[0162] For a light-emitting device in one embodiment of the present invention, it is possible to employ a color filter method in which full-color images are displayed using a combination of a color filter and a light-emitting element that emits light of a single color such as white.

Alternatively, a method in which a full-color image is displayed with the use of a plurality of light-emitting elements emitting light with different hues can be employed. This method is referred to as a separate coloring method because EL layers, which are each placed between a pair of electrodes in a light-emitting element, are separately colored with their corresponding colors.

[0163] In the separate coloring method, in general, EL layers are separately deposited by vapor deposition with use of a mask such as a metal mask. Thus, the size of pixels depends on the accuracy of separate deposition of the EL layers by vapor deposition. On the other hand, unlike the separate coloring method, EL layers do not need to be separately formed in the color filter method. Accordingly, in the case of the color filter method, as compared to the separate coloring method, the pixel can be easily reduced in size, and the pixel portion with high high-definition can be formed.

[0164] In the top-emission structure, light emitted from a light-emitting element is not blocked by an element such as a wiring, a transistor, or a capacitor, so that the efficiency of light extraction from a pixel can be made higher than that in the bottom-emission structure. Accordingly, a top emission type light-emitting device can have high luminance even when the light-emitting element is supplied with low current value, and has an advantage in that the lifetime of the light-emitting element is prolonged.

[0165] In one embodiment of the present invention, the light-emitting device may have a microcavity (micro optical resonator) structure in which light emitted from an EL layer resonates within a light-emitting element. With a microcavity structure, the light-extraction efficiency of light with a particular wavelength from the light-emitting element can be increased, so that the luminance and the color purity of the pixel portion can be improved.

<Cross-Sectional Structure of Light-Emitting Device>

[0166] FIG. **16** illustrates an example of a cross-sectional structure of a pixel portion in a light-emitting device corresponding to the semiconductor device of one embodiment of the present invention.

[0167] Specifically, the light-emitting device in FIG. **16** includes a transistor **42** over a substrate **400**. FIG. **16** shows an example in which the transistor **42** which has the same structure as the transistor **10** in FIGS. **2A** to **2D** is used in the light-emitting device; however, in one embodiment of the present invention, any of the transistors **10** in FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** can be used for the

light-emitting device.

[0168] An insulating film **420** is provided over the transistor **42**, and a conductive film **424** is provided over the insulating film **420**. The conductive film **424** is connected to a conductive film **404** serving as a source electrode or a drain electrode of the transistor **42**, through an opening portion of the insulating film **420**.

[0169] An insulating film **425** is provided over the insulating film **420** and the conductive film **424**. The insulating film **425** has an opening portion in a region overlapping the conductive film **424**. Over the insulating film **425**, an insulating film **426** is provided in a position that is different from the position of the opening portion of the insulating film **425**. An EL layer **427** and a conductive film **428** are sequentially stacked over the insulating films **425** and **426**. A portion in which the conductive films **424** and **428** overlap each other with the EL layer **427** positioned therebetween functions as a light-emitting element **43**. One of the conductive films **424** and **428** functions as an anode, and the other of the conductive films **424** and **428** functions as a cathode.

[0170] The light-emitting device includes a substrate **430** that faces the substrate **400** with the light-emitting element **43** positioned therebetween. A blocking film **431** that has a function of blocking light is provided over the substrate **430**, i.e., over a surface of the substrate **430** that is close to the light-emitting element **43**. The blocking film **431** includes an opening portion in a region overlapping the light-emitting element **43**. In the opening that overlaps the light-emitting element **43**, a coloring layer **432** that transmits visible light in a specific wavelength range is provided over the substrate **430**.

<Configuration Example of Sequential Circuit>

[0171] Next, a configuration example of a sequential circuit using any of the transistors **10** in FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** is described.

[0172] FIG. **17A** schematically illustrates the positions of a variety of wirings connected to a sequential circuit **80**. FIG. **17B** illustrates an example of the circuit configuration of the sequential circuit **80**. The sequential circuit **80** in FIG. **17B** includes p-channel transistors **81** to **85** and n-channel transistors **86** to **90**. Any of the structures of the transistors **10** in FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** is applicable to the transistors **81** to **90**.

[0173] In the sequential circuit **80**, the transistor **81**, the transistor **82**, the transistor **86**, and the transistor **87** form a clocked inverter in which whether a signal is output is controlled in accordance with signals supplied to a wiring **c1** and a wiring **c2**.

[0174] Specifically, a gate of the transistor **81** is connected to the wiring **c2**; one of a source and a drain of the transistor **81** is connected to the wiring **74**; and the other of the source and the drain of the transistor **81** is connected to one of a source and a drain of the transistor **82**. A gate of the transistor **82** is connected to a wiring **in**, and the other of the source and the drain of the transistor **82** is connected to a gate of the transistor **85** and a gate of the transistor **90**. A gate of the transistor **87** is connected to the wiring **c1**; one of a source and a drain of the transistor **87** is connected to the wiring **75**; and the other of the source and the drain of the transistor **87** is connected to one of a source and a drain of the transistor **86**. A gate of the transistor **86** is connected to the wiring **in**, and the other of the source and the drain of the transistor **86** is connected to the gate of the transistor **85** and the gate of the transistor **90**.

[0175] In the sequential circuit **80**, the transistor **83**, the transistor **84**, the transistor **88**, and the transistor **89** form a clocked inverter in which whether a signal is output is controlled in accordance with signals supplied to the wiring **c1** and the wiring **c2**.

[0176] Specifically, a gate of the transistor **83** is connected to the wiring **c1**; one of a source and a drain of the transistor **83** is connected to a wiring **76**; and the other of the source and the drain of the transistor **83** is connected to one of a source and a drain of the transistor **84**. A gate of the transistor **84** is connected to a wiring **out**, and the other of the source and the drain of the transistor

84 is connected to the gate of the transistor **85** and the gate of the transistor **90**. A gate of the transistor **89** is connected to the wiring **c2**; one of a source and a drain of the transistor **89** is connected to a wiring **77**; and the other of the source and the drain of the transistor **89** is connected to one of a source and a drain of the transistor **88**. A gate of the transistor **88** is connected to the wiring out, and the other of the source and the drain of the transistor **88** is connected to the gate of the transistor **85** and the gate of the transistor **90**.

[0177] In the sequential circuit **80**, the transistor **85** and the transistor **90** form an inverter.

[0178] Specifically, one of a source and a drain of the transistor **85** is connected to a wiring **78**, and the other of the source and the drain of the transistor **85** is connected to the wiring out. One of a source and a drain of the transistor **90** is connected to a wiring **79**, and the other of the source and the drain of the transistor **90** is connected to the wiring out.

[0179] A low-level potential VSS is supplied to the wiring **75**, the wiring **77**, and the wiring **79**; and a high-level potential VDD is supplied to the wiring **74**, the wiring **76**, and the wiring **78**.

[0180] The on-state current of any of the transistors **10** in FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** can be large. Therefore, the use of any of the transistors **10** in FIGS. **1A** to **1D**, FIGS. **2A** to **2D**, FIGS. **3A** to **3D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** as any of the transistors **81** to **90** in the sequential circuit **80** enables high-speed operation of the sequential circuit **80**.

Furthermore, the off-state current of any of the transistors **10** in FIGS. **2A** to **2D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** can be small. Therefore, the use of any of the transistors **10** in FIGS. **2A** to **2D**, FIGS. **4A** to **4D**, FIGS. **5A** to **5D**, FIGS. **6A** to **6D**, and FIGS. **7A** to **7D** as any of the transistors **81** to **90** can reduce leakage current flowing between the wirings **75**, **77**, and **79** and the wirings **74**, **76**, and **78**, resulting in a reduction in power consumption of the sequential circuit **80**.

<Configuration Example of Driver Circuit>

[0181] Next, FIG. **18** illustrates a block diagram showing a configuration example of a signal line driver circuit using the sequential circuit **80** illustrated in FIGS. **17A** and **17B**. Although the block diagram shows elements classified according to their functions in independent blocks, it may be practically difficult to completely separate the elements according to their functions and, in some cases, one element may be involved in a plurality of functions.

[0182] In the signal line driver circuit illustrated in FIG. **18**, a shift register is formed using a plurality of sequential circuits **80**. In each of the plurality of sequential circuits **80**, a start pulse signal SSP or a signal of the wiring out connected to the sequential circuit **80** in the previous stage is input to the wiring in. A clock signal SCK is input to one of the wiring **c1** and the wiring **c2**, and a clock signal SCKb, which is obtained by inverting the logic value of the clock signal SCK is input to the other of the wiring **c1** and the wiring **c2**.

[0183] The signal input to the wiring in and the signal input to the wiring out of each of the plurality of sequential circuits **80** are input to a pair of input terminals included in the corresponding one of a plurality of NANDs **40**. A signal output from an output terminal of each of the plurality of NANDs **40** is input to one of a pair of input terminals of the corresponding one of a plurality of NORs **41**. Furthermore, the signal output from the output terminal of each of the plurality of NANDs **40** is input to the other of the pair of input terminals of the corresponding one of the plurality of NORs **41** through a buffer **44**. A signal output from an output terminal of each of the plurality of NORs **41** is input to a first terminal of the corresponding one of a plurality of transmission gates **47** through a buffer **45**. Furthermore, the signal output from the output terminal of each of the plurality of NORs **41** is input to a second terminal of the corresponding one of the plurality of transmission gates **47** through a buffer **46**.

[0184] The transmission gates **47** each have a function of controlling supply of an image signal Video that is input to an input terminal of the transmission gate **47**, in response to signals input to the first and second terminals.

[0185] Next, FIG. 19 is a block diagram showing a configuration example of a scan line driver circuit using the sequential circuits 80 in FIGS. 17A and 17B.

[0186] In the signal line driver circuit illustrated in FIG. 19, a shift register is formed using a plurality of sequential circuits 80. In each of the plurality of sequential circuits 80, a start pulse signal GSP or a signal of the wiring out connected to the sequential circuit 80 in the previous stage is input to the wiring in. A clock signal GCK is input to one of the wiring c1 and the wiring c2, and a clock signal GCKb, which is obtained by inverting the logic value of the clock signal GCK is input to the other of the wiring c1 and the wiring c2.

[0187] A signal input to the wiring in and a signal input to the wiring out of each of the plurality of sequential circuits 80 are input to a pair of input terminals of the corresponding one of a plurality of NANDs 48. A signal output from an output terminal of each of the plurality of NANDs 48 is input to one of a pair of input terminals of the corresponding one of a plurality of NORs 49. A signal PWC is input to the other of the pair of input terminals of each of the plurality of NORs 49.

Specifically, FIG. 19 shows an example in which a signal output from the output terminal of one NAND 48 is input to one of the pair of input terminals of each of six NORs 49. Signals PWC1 to PWC6 are input to the other of the pair of input terminals of each of the six NORs 49. Signals output from output terminals of the plurality of NORs 49 are input to the plurality of wirings GL through buffers 50.

[0188] Note that any of the transistors 10 illustrated in FIGS. 1A to 1D, FIGS. 2A to 2D, FIGS. 3A to 3D, FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D can be used not only in the sequential circuit 80 but also in a variety of circuits included in the signal line driver circuit in FIG. 18 and a variety of circuits included in the scan line driver circuit in FIG. 19. The on-state current of any of the transistors 10 in FIGS. 1A to 1D, FIGS. 2A to 2D, FIGS. 3A to 3D, FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D can be large. Therefore, the use of any of the transistors 10 in FIGS. 1A to 1D, FIGS. 2A to 2D, FIGS. 3A to 3D, FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D for the circuits included in the signal line driver circuit or the scan line driver circuit enables high-speed operation of the signal line driver circuit or the scan line driver circuit. Furthermore, the off-state current of any of the transistors 10 in FIGS. 2A to 2D, FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D can be small. Therefore, the use of any of the transistors 10 in FIGS. 2A to 2D, FIGS. 4A to 4D, FIGS. 5A to 5D, FIGS. 6A to 6D, and FIGS. 7A to 7D for the circuits included in the signal line driver circuit or the scan line driver circuit can reduce the power consumption of the signal line driver circuit or the scan line driver circuit.

<Exterior Appearance of Light-Emitting Device>

[0189] FIG. 20 is a perspective view illustrating an example of the exterior appearance of a light-emitting device corresponding to one mode of a semiconductor device of the present invention. The light-emitting device shown in FIG. 20 includes a panel 1601; a circuit board 1602 including a controller, a power circuit, an image processing circuit, an image memory, a CPU, and the like; and a connection portion 1603. The panel 1601 includes a pixel portion 1604 including a plurality of pixels, a driver circuit 1605 that selects a plurality of pixels row by row, and a driver circuit 1606 that controls supply of image signals Sig to the pixels in a selected row.

[0190] A variety of signals and power supply potentials are input from the circuit board 1602 to the panel 1601 through the connection portion 1603. As the connecting portion 1603, a flexible printed circuit (FPC) or the like can be used. In the case where a COF tape is used as the connection portion 1603, part of circuits in the circuit board 1602 or part of the driver circuit 1605 or the driver circuit 1606 included in the panel 1601 may be formed on a chip separately prepared, and the chip may be connected to the COF tape by chip on film (COF).

<Structure Example of Electronic Appliance>

[0191] A semiconductor device of one embodiment of the present invention can be used for display devices, laptop computers, or image reproducing devices provided with recording media (typically,

devices which reproduce the content of recording media such as digital versatile discs (DVDs) and have displays for displaying the reproduced images). Furthermore, as an electronic appliance which can include the semiconductor device of one embodiment of the present invention, mobile phones, portable game machines, personal digital assistants, e-book readers, cameras such as video cameras and digital still cameras, goggle-type displays (head mounted displays), navigation systems, audio reproducing devices (e.g., car audio systems and digital audio players), copiers, facsimiles, printers, multifunction printers, automated teller machines (ATM), vending machines, and the like can be given. FIGS. 21A to 21F show specific examples of these electronic appliances.

[0192] FIG. 21A shows a display device including a housing 5001, a display portion 5002, a supporting base 5003, and the like. The semiconductor device of one embodiment of the present invention can be used for the display portion 5002 or a variety of circuits. Note that the category of the display device includes all the display devices for displaying information, such as display devices for a personal computer, TV broadcast reception, advertisement display, and the like.

[0193] FIG. 21B shows a portable digital assistant including a housing 5101, a display portion 5102, an operation key 5103, and the like. The semiconductor device of one embodiment of the present invention can be used for the display portion 5102 or a variety of circuits.

[0194] FIG. 21C shows a display device which includes a housing 5701 having a curved surface, a display portion 5702, and the like. The semiconductor device of one embodiment of the present invention can be used for the display portion 5702 or a variety of circuits. When a flexible substrate is used for the semiconductor device of one embodiment of the present invention, it is possible to use the semiconductor device as the display portion 5702 supported by the housing 5701 having a curved surface. Consequently, it is possible to provide a user-friendly display device that is flexible and lightweight.

[0195] FIG. 21D shows a portable game machine including a housing 5301, a housing 5302, a display portion 5303, a display portion 5304, a microphone 5305, speakers 5306, an operation key 5307, a stylus 5308, and the like. The semiconductor device of one embodiment of the present invention can be used for the display portion 5303, the display portion 5304, or the variety of circuits. Note that although the portable game machine shown in FIG. 21D includes two display portions, the display portions 5303 and 5304, the number of display portions included in the portable game machine is not limited thereto.

[0196] FIG. 21E shows an e-book reader which includes a housing 5601, a display portion 5602, and the like. The semiconductor device of one embodiment of the present invention can be used for the display portion 5602 or a variety of circuits. When a flexible substrate is used, the display portion can have flexibility, so that it is possible to provide a user-friendly e-book reader that is flexible and lightweight.

[0197] FIG. 21F shows a mobile phone which includes a display portion 5902, a microphone 5907, a speaker 5904, a camera 5903, an external connection port 5906, and an operation button 5905 in a housing 5901. The semiconductor device of one embodiment of the present invention can be used for the display portion 5902 or the variety of circuits. When the semiconductor device of one embodiment of the present invention is provided over a flexible substrate, the semiconductor device can be used as the display portion 5902 having a curved surface, as illustrated in FIG. 21F.

EXPLANATION OF REFERENCE

[0198] 1: structure example; 2: structure example; 3: structure example; 4: structure example; 5: structure example; 6: structure example; 7: structure example; 10: transistor; 10a: transistor; 10b: transistor; 10c: transistor; 10N: transistor; 10P: transistor; 11: substrate; 12: semiconductor film; 12a: channel formation region; 12b: impurity region; 12c: impurity region; 13: insulating film; 13a: insulating film; 13c: insulating film; 14: conductive film; 15: conductive film; 16: insulating film; 17: conductive film; 17a: conductive film; 17b: conductive film; 17c: conductive film; 18: opening portion; 18a: opening portion; 18b: opening portion; 18c: opening portion; 19: opening portion; 19a: opening portion; 19b: opening portion; 19c: opening portion; 20: conductive film; 21:

insulating film; 22: opening portion; 23: opening portion; 24: conductive film; 25: opening portion; 26: conductive film; 27: conductive film; 28: opening portion; 29: opening portion; 30: conductive film; 31: conductive film; 32: conductive film; 33: conductive film; 40: NAND; 42: transistor; 43: light-emitting element; 44: buffer; 45: buffer; 46: inverter; 47: transmission gate; 48: NAND; 50: buffer; 55: pixel; 56: transistor; 57: capacitor; 60: liquid crystal element; 70: semiconductor display device; 71: pixel portion; 72: scan line driver circuit; 73: signal line driver circuit; 74: wiring; 75: wiring; 76: wiring; 77: wiring; 78: wiring; 79: wiring; 80: sequential circuit; 81: transistor; 82: transistor; 83: transistor; 84: transistor; 85: transistor; 86: transistor; 87: transistor; 88: transistor; 89: transistor; 90: transistor; 95: transistor; 96: transistor; 97: capacitor; 98: light-emitting element; 300: substrate; 301: insulating film; 302: conductive film; 303: conductive film; 304: insulating film; 305: semiconductor film; 306: semiconductor film; 307: semiconductor film; 308: insulating film; 309: conductive film; 310: conductive film; 311: resist; 312: impurity region; 313: resist; 314: impurity region; 320: insulating film; 321: conductive film; 322: conductive film; 400: substrate; 404: conductive film; 420: insulating film; 424: conductive film; 425: insulating film; 426: insulating film; 427: EL layer; 428: conductive film; 430: substrate; 431: blocking film; 432: coloring layer; 501: conductive film; 502: semiconductor film; 503: conductive film; 504: conductive film; 505: conductive film; 506: conductive film; 507: semiconductor film; 508: conductive film; 509: conductive film; 510: conductive film; 511: conductive film; 1601: panel; 1602: circuit substrate; 1603: connection portion; 1604: pixel portion; 1605: driver circuit; 1606: driver circuit; 5001: housing; 5002: display portion; 5003: supporting base; 5101: housing; 5102: display portion; 5103: operation key; 5301: housing; 5302: housing; 5303: display portion; 5304: display portion; 5305: microphone; 5306: speaker; 5307: operation key; 5308: stylus; 5601: housing; 5602: display portion; 5701: housing; 5702: display portion; 5901: housing; 5902: display portion; 5903: camera; 5904: speaker; 5905: button; 5906: external connection port; 5907: microphone

[0199] This application is based on Japanese Patent Application serial no. 2013-190275 filed with Japan Patent Office on Sep. 13, 2013, the entire contents of which are hereby incorporated by reference.

Claims

1. A light-emitting device comprising: a pixel comprising: a first transistor; a second transistor; a light-emitting element; a capacitor; a wiring to which an image signal is input; a scan line; and a power source line, wherein one of a source and a drain of the first transistor is always conductive to the wiring to which the image signal is input, wherein the other of the source and the drain of the first transistor is always conductive to a gate of the second transistor, wherein a gate of the first transistor is always conductive to the scan line, wherein one of a source and a drain of the second transistor is always conductive to the power source line, wherein the other of the source and the drain of the second transistor is always conductive to a pixel electrode of the light-emitting element, wherein the capacitor is configured to retain a voltage between the gate of the second transistor and the pixel electrode of the light-emitting element, wherein a first semiconductor film includes a channel formation region of the first transistor and is configured to be a first electrode of the capacitor, wherein a second semiconductor film includes a channel formation region of the second transistor, wherein a first conductive film is configured to be the gate of the first transistor and the scan line and comprises a region over the first semiconductor film, wherein a second conductive film is configured to be the wiring to which the image signal is input, wherein a third conductive film is configured to be a second electrode of the capacitor, wherein each of a fourth conductive film and a fifth conductive film is configured to be the power source line, wherein the second conductive film comprises a region crossing the first conductive film and a region crossing the fourth conductive film, wherein the fifth conductive film comprises a region crossing the first

conductive film and a region crossing the fourth conductive film, wherein the third conductive film and the first conductive film do not overlap with each other, and wherein the third conductive film and the fourth conductive film do not overlap with each other.

2. The light-emitting device according to claim 1, wherein the third conductive film and the second conductive film do not overlap with each other.

3. The light-emitting device according to claim 1, wherein the first semiconductor film comprises a first region overlapping with the third conductive film, and wherein in a plan view, the first region is between the channel formation region of the first transistor and the channel formation region of the second transistor.

4. The light-emitting device according to claim 1, wherein the first semiconductor film comprises a first region overlapping with the third conductive film, and wherein in a plan view, the first region is between the second conductive film and the fifth conductive film.

5. The light-emitting device according to claim 1, wherein the third conductive film and the second conductive film do not overlap with each other, wherein the first semiconductor film comprises a first region overlapping with the third conductive film, and wherein in a plan view, the first region is between the channel formation region of the first transistor and the channel formation region of the second transistor.

6. The light-emitting device according to claim 1, wherein the third conductive film and the second conductive film do not overlap with each other, wherein the first semiconductor film comprises a first region overlapping with the third conductive film, and wherein in a plan view, the first region is between the second conductive film and the fifth conductive film.
