

```
EDGE#conf t
Enter configuration commands, one per line. End with CNTL/Z.
EDGE(config)#
*Sep 24 13:31:02.794: %PNP-6-PNP_DISCOVERY_STOPPED: PnP Discovery stopped (Config Wizard)
EDGE(config)#int e0/0
EDGE(config-if)#ip add 172.18.0.2 255.255.255.252
EDGE(config-if)#ip nat inside
EDGE(config-if)#no sh
EDGE(config-if)#e
*Sep 24 13:33:12.102: %LINEPROTO-5-UPDOWN: Line protocol on Interface NVI0, changed state to up
EDGE(config-if)#ex
EDGE(config)#int e0/1
EDGE(config-if)#ip add 212.41.56.1 255.255.255.0
EDGE(config-if)#ip nat outside
EDGE(config-if)#no sh
EDGE(config-if)#ex
EDGE(config)#exit
EDGE#
*Sep 24 13:34:04.628: %SYS-5-CONFIG_I: Configured from console by console
EDGE#conf t
Enter configuration commands, one per line. End with CNTL/Z.
EDGE(config)#ip route 0.0.0.0 0.0.0.0 212.41.56.2
EDGE(config)#exit
EDGE#
*Sep 24 13:34:26.140: %SYS-5-CONFIG_I: Configured from console by console
EDGE#conf t
Enter configuration commands, one per line. End with CNTL/Z.
EDGE(config)#access-list 1 permit 172.16.0.0 0.0.255.255
EDGE(config)#access-list 1 permit 172.17.0.0 0.0.255.255
EDGE(config)#ip nat inside source list 1 int e0/1 overload
EDGE(config)#exit
EDGE#
EDGE#
EDGE#
*Sep 24 13:36:10.991: %SYS-5-CONFIG_I: Configured from console by console
EDGE#show ip route
Codes: L - local, C - connected, S - static, R - RIP, M - mobile, B - BGP
        D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
        N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
        E1 - OSPF external type 1, E2 - OSPF external type 2
        i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
        ia - IS-IS inter area, * - candidate default, U - per-user static route
        o - ODR, P - periodic downloaded static route, H - NHRP, l - LISP
        a - application route
        + - replicated route, % - next hop override, p - overrides from PfR

Gateway of last resort is 212.41.56.2 to network 0.0.0.0
```

```
*Sep 24 13:34:04.628: %SYS-5-CONFIG_I: Configured from console by console
EDGE#conf t
```

```
Enter configuration commands, one per line. End with CNTL/Z.
```

```
EDGE(config)#ip route 0.0.0.0 0.0.0.0 212.41.56.2
```

```
EDGE(config)#exit
```

```
EDGE#
```

```
*Sep 24 13:34:26.140: %SYS-5-CONFIG_I: Configured from console by console
```

```
EDGE#conf t
```

```
Enter configuration commands, one per line. End with CNTL/Z.
```

```
EDGE(config)#access-list 1 permit 172.16.0.0 0.0.255.255
```

```
EDGE(config)#access-list 1 permit 172.17.0.0 0.0.255.255
```

```
EDGE(config)#ip nat inside source list 1 int e0/1 overload
```

```
EDGE(config)#exit
```

```
EDGE#
```

```
EDGE#
```

```
EDGE#
```

```
*Sep 24 13:36:10.991: %SYS-5-CONFIG_I: Configured from console by console
```

```
EDGE#show ip route
```

```
Codes: L - local, C - connected, S - static, R - RIP, M - mobile, B - BGP
```

```
D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
```

```
N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
```

```
E1 - OSPF external type 1, E2 - OSPF external type 2
```

```
i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
```

```
ia - IS-IS inter area, * - candidate default, U - per-user static route
```

```
o - ODR, P - periodic downloaded static route, H - NHRP, l - LISP
```

```
a - application route
```

```
+ - replicated route, % - next hop override, p - overrides from PfR
```

```
Gateway of last resort is 212.41.56.2 to network 0.0.0.0
```

```
S* 0.0.0.0/0 [1/0] via 212.41.56.2
```

```
172.18.0.0/16 is variably subnetted, 2 subnets, 2 masks
```

```
C 172.18.0.0/30 is directly connected, Ethernet0/0
```

```
L 172.18.0.2/32 is directly connected, Ethernet0/0
```

```
212.41.56.0/24 is variably subnetted, 2 subnets, 2 masks
```

```
C 212.41.56.0/24 is directly connected, Ethernet0/1
```

```
L 212.41.56.1/32 is directly connected, Ethernet0/1
```

```
EDGE#conf t
```

```
Enter configuration commands, one per line. End with CNTL/Z.
```

```
EDGE(config)#ip route 172.16.0.0 255.255.255.0 172.18.0.1
```

```
% Incomplete command.
```

```
EDGE(config)#ip route 172.16.0.0 255.255.255.0 172.18.0.1
```

```
EDGE(config)#ip route 172.17.0.0 255.255.255.0 172.18.0.1
```

```
EDGE(config)#exit
```

```
EDGE#
```

```
*Sep 24 13:38:14.093: %SYS-5-CONFIG_I: Configured from console by console
```

```
EDGE#
```

CORE



```
CORE#
CORE#
CORE#conf t
Enter configuration commands, one per line. End with CNTL/Z.
CORE(config)#int e0/0
CORE(config-if)#switchport trunk encapsulation dot1q
CORE(config-if)#switchport mode trunk
CORE(config-if)#exit
CORE(config)#
CORE(config)#exit
CORE#
*Sep 24 13:26:54.055: %SYS-5-CONFIG_I: Configured from console by console
CORE#conf t
Enter configuration commands, one per line. End with CNTL/Z.
CORE(config)#vlan 100
CORE(config-vlan)#exit
CORE(config)#vlan 200
CORE(config-vlan)#exit
CORE(config)#
CORE(config)#int vlan 100
CORE(config-if)#i
*Sep 24 13:27:17.232: %LINEPROTO-5-UPDOWN: Line protocol on Interface Vlan100, changed state to down
CORE(config-if)#ip add 172.16.0.1 255.255.255.0
CORE(config-if)#no sh
CORE(config-if)#ex
CORE(config)#int
*Sep 24 13:27:34.483: %LINK-3-UPDOWN: Interface Vlan100, changed state to up
*Sep 24 13:27:35.483: %LINEPROTO-5-UPDOWN: Line protocol on Interface Vlan100, changed state to up
CORE(config)#int vlan 200
CORE(config-if)#
*Sep 24 13:27:39.525: %LINEPROTO-5-UPDOWN: Line protocol on Interface Vlan200, changed state to down
CORE(config-if)#ip add 172.17.0.1 255.255.255.0
CORE(config-if)#exit
CORE(config)#int vlan 200
CORE(config-if)#no sh
CORE(config-if)#ex
CORE(config)#exit
CORE#
*Sep 24 13:28:20.578: %LINK-3-UPDOWN: Interface Vlan200, changed state to up
*Sep 24 13:28:21.578: %LINEPROTO-5-UPDOWN: Line protocol on Interface Vlan200, changed state to up
CORE#
CORE#
*Sep 24 13:28:21.609: %SYS-5-CONFIG_I: Configured from console by console
CORE#conf t
Enter configuration commands, one per line. End with CNTL/Z.
CORE(config)#int e0/1
CORE(config-if)#no switchport
CORE(config-if)#ip add 17
```

```
CORE(config)#int e0/1
CORE(config-if)#no switchport
CORE(config-if)#ip add 17
*Sep 24 13:28:41.207: %LINK-3-UPDOWN: Interface Ethernet0/1, changed state to up
*Sep 24 13:28:42.207: %LINEPROTO-5-UPDOWN: Line protocol on Interface Ethernet0/1, changed state to up
CORE(config-if)#ip add 172.18.0.1 255.255.255.252
CORE(config-if)#no sh
CORE(config-if)#ex
CORE(config)#ip routing
CORE(config)#exit
CORE#
*Sep 24 13:28:59.170: %SYS-5-CONFIG_I: Configured from console by console
CORE#conf t
Enter configuration commands, one per line. End with CNTL/Z.
CORE(config)#ip route 0.0.0.0 0.0.0.0 172.18.0.2
CORE(config)#exit
CORE#
CORE#
CORE#
*Sep 24 13:29:20.835: %SYS-5-CONFIG_I: Configured from console by console
CORE#show ip route
Codes: L - local, C - connected, S - static, R - RIP, M - mobile, B - BGP
       D - EIGRP, EX - EIGRP external, O - OSPF, IA - OSPF inter area
       N1 - OSPF NSSA external type 1, N2 - OSPF NSSA external type 2
       E1 - OSPF external type 1, E2 - OSPF external type 2
       i - IS-IS, su - IS-IS summary, L1 - IS-IS level-1, L2 - IS-IS level-2
       ia - IS-IS inter area, * - candidate default, U - per-user static route
       o - ODR, P - periodic downloaded static route, H - NHRP, l - LISP
       a - application route
       + - replicated route, % - next hop override, p - overrides from PfR

Gateway of last resort is 172.18.0.2 to network 0.0.0.0

S*    0.0.0.0/0 [1/0] via 172.18.0.2
      172.16.0.0/16 is variably subnetted, 2 subnets, 2 masks
C      172.16.0.0/24 is directly connected, Vlan100
L      172.16.0.1/32 is directly connected, Vlan100
      172.17.0.0/16 is variably subnetted, 2 subnets, 2 masks
C      172.17.0.0/24 is directly connected, Vlan200
L      172.17.0.1/32 is directly connected, Vlan200
      172.18.0.0/16 is variably subnetted, 2 subnets, 2 masks
C      172.18.0.0/30 is directly connected, Ethernet0/1
L      172.18.0.1/32 is directly connected, Ethernet0/1
CORE#
*Sep 24 13:30:21.475: %PNP-6-PNP_DISCOVERY_STOPPED: PnP Discovery stopped (Config Wizard)
CORE#
```

L2-SWITCH

```
Trying 49.204.127.18...
Connected to labs.surennetwork.com.
Escape character is '^]'.

L2-SWITCH#
L2-SWITCH#
L2-SWITCH#conf t
Enter configuration commands, one per line.  End with CNTL/Z.
L2-SWITCH(config)#vlan 100
L2-SWITCH(config-vlan)#name Design
L2-SWITCH(config-vlan)#exit
L2-SWITCH(config)#vlan 200
L2-SWITCH(config-vlan)#name Dev
L2-SWITCH(config-vlan)#exit
L2-SWITCH(config)#int e0/0
L2-SWITCH(config-if)#switchport access vlan 100
L2-SWITCH(config-if)#exit
L2-SWITCH(config)#int e0/1
L2-SWITCH(config-if)#switchport access vlan 100
L2-SWITCH(config-if)#
*Sep 24 13:24:08.655: %PNP-6-PNP_DISCOVERY_STOPPED: PnP Discovery stopped (Config Wizard)
L2-SWITCH(config-if)#exit
L2-SWITCH(config)#int e0/2
L2-SWITCH(config-if)#switchport access vlan 200
L2-SWITCH(config-if)#exit
L2-SWITCH(config)#int e0/3
L2-SWITCH(config-if)#switchport access vlan 200
L2-SWITCH(config-if)#int e1/0
L2-SWITCH(config-if)#switchport trunk encapsulation dot1q
L2-SWITCH(config-if)#switchport mode trunk
L2-SWITCH(config-if)#exit
L2-SWITCH(config)#
L2-SWITCH(config)#
L2-SWITCH(config)#exit
L2-SWITCH#
L2-SWITCH#
L2-SWITCH#
*Sep 24 13:26:02.270: %SYS-5-CONFIG_I: Configured from console by console
L2-SWITCH#
```







