LED assembly polarity

RheoBoard v1.05 | TOP side | Updated 2026-10-24

11 x Yongyu SZYY0603R / JLCPCB C434419

Pin 1 = A / anode (+). Pin 2 = K / cathode (-).
Schematic pins, PCB pads and manufacturer terminal numbers now agree.
The green cathode mark goes toward pad 2 and the silkscreen end bar.

Reference	Top view	Pin 1 / A (+), X / Y mm	Pin 2 / K (-), X / Y mm
D6		158.4450 / 54.0074	158.4450 / 52.2574
D7		155.0750 / 54.0074	155.0750 / 52.2574
D8		151.8000 / 54.0074	151.8000 / 52.2574
D13		171.2550 / 100.7500	169.5050 / 100.7500
D14		139.2875 / 100.7500	137.5375 / 100.7500
D15		162.7000 / 72.1030	162.7000 / 70.3530
D17		125.4153 / 136.9512	125.4153 / 138.7012
D19		157.6832 / 137.0412	157.6832 / 138.7912
D33		135.2679 / 71.0859	133.6929 / 71.0859
D34		135.2938 / 58.4583	133.7188 / 58.4583
D35		107.5194 / 64.0595	105.9444 / 64.0595

Coordinate and placement convention

Top/component view: right is +X, down is +Y. Diagrams show board orientation.
Pad coordinates above are KiCad coordinates; the CPL uses inverted Y.
Use the supplied CPL unchanged. Check these polarity targets in JLCPCB placement preview before ordering; no unverified 180-degree correction has been applied.

Source: Yongyu SZYY0603 red LED specification, page 2; manufacturer package/polarity drawing.
Open manufacturer datasheet