ME 5309 – Mid-Semester Examination

Answer Booklet

Instructions: Attempt any three questions. Each question carries 10 marks. Show working where appropriate.

Question 1 [10 marks]

Q1(a) [4 marks]

$$f_x = 3200 pixels; fieldofview = 160mm; 1pixel = 0.125mm$$

Q1(b) [3 marks]

Q1(c) [3 marks]

$$F = 0.8187, G = 0.0906$$

Question 2 [10 marks]

Q2(a) [2 marks]

At equilibrium the velocity should be zero. The torque and gravity torque must balance.

Q2(b) [2 marks]

$$A = [[0, 1], [-mg\ell sin(60^\circ)/J, -b/J]] = [[0, 1], [-106.2, -2.5]],$$
$$B = [[0], [50]]$$

Q2(c) [4 marks]

At rest, $\dot{\theta} = \ddot{\theta} = 0$, so the torque balance is Kp(θd-θss) = mgℓ sin θss. With Kp = 50, θd = π/2 and mgℓ = 2.4525, solve 50(π/2-θss) = 2.4525 sin θss. This gives θss approximately 1.52181 rad = 87.193°, so the error is 90°-87.193° = 2.807°; it is not zero.

Rearranging the steady-state equation gives $50(\pi/2 - \theta_{ss}) = 2.4525 \sin\theta_{ss}$. I used radians in the equation. Solving numerically gives $\theta_{ss} \approx 1.522$ rad $\approx 87.19^\circ$, so the gap from 90° is about 2.81°.

Q2(d) [2 marks]

With gravity compensation, the gravity term cancels the plant's mgℓ sin θ term. At rest, Kp(θd-θss)=0, so θss=θd and the steady-state error is zero. The linearised gravity stiffness term is also cancelled, so the closed-loop poles generally change; the stiffness contribution mgℓ cos θd is removed.

The compensation term cancels the nominal gravity torque in the plant model. At steady state the proportional term must then be zero, which requires $\theta_d - \theta_{ss} = 0$. This does not mean

the transient response is unchanged: removing the gravity derivative changes the linearized stiffness.

Question 4 [10 marks]

Q4(a) [2 marks]

Poles are -2±2j and Nff=8.

Q4(b) [2 marks]

With actual b=0.75 and unchanged Nff=8, k_1=2, the steady-state relation is θss = bNff/(c+bk_1) = 0.75x8/(6+0.75x2)=6/7.5=0.8. For r=1, percentage error = (1-0.8)x100%=20%.

With the actual gain, the steady-state output is $y_{ss} = b_{actual} N_{ff} r/(c+b_{actual} k_1)$ for the stated setup. Substituting the given numbers gives $y_{ss} = 0.8$ for a unit reference. Therefore $e_{ss} = 1 - 0.8 = 0.2$, i.e. a 20% error.

Q4(c) [4 marks]

With $\dot{\xi}$=r-θ and u=-k_1θ-$k_2\dot{\theta}$+K_Iξ, the homogeneous closed-loop characteristic polynomial is s^3+(a+bk_2)s^2+(c+
Desired polynomial: (s+4)[(s+2)²+4]=(s+4)(s^2+4s+8)=s^3+8s^2+24s+32. For a=2,b=1,c=6, matching coefficients gives k_2=6, k_1=18 and K_I=32.

First multiply $(s+4)(s^2+4s+8) = s^3+8s^2+24s+32$. Comparing this with the augmented characteristic polynomial gives $k_2 = 6$, $k_1 = 18$, and $K_I = 32$. I checked the coefficients in descending powers of s.

Q4(d) [2 marks]

Integral action removes steady-state error, although this only holds for the nominal values of b and c. Saturation can cause windup, which should be handled by anti-windup.