ME 5309 – Mid-Semester Examination

Answer Booklet

Instructions: Attempt any three questions. Each question carries 10 marks. Show working where appropriate.

Question 1 [10 marks]

Q1(a) [4 marks]

(i) f_x = 16/0.005 = 3200 pixels. (ii) Sensor width = 6.4 mm. I used W = 2Z tan(f/(2Z)) and obtained about 16 mm; pixel scale = 16/1280 = 0.0125 mm/pixel.

Q1(b) [3 marks]

ADC step = 5/4096 = 1.2207 mV. I divide by 0.1 mV/N, giving ΔF = 12.207 N.

Q1(c) [3 marks]

$$F = e^(AT) = e^(-0.2) = 0.818731$$

Question 2 [10 marks]

Q2(a) [2 marks]

$\dot{x}_1 = x_2$ and $\dot{x}_2 = (\tau - b\,x_2 + mg\ell \sin\theta)/J$. At equilibrium:

$$_0 = -mg\ell sin\theta_e,$$

an equilibrium exists for $|\tau_0|$ less than or equal to 2.4525 N m

Q2(b) [2 marks]

$$A = [[0, 1], [-61.3125, -2.5]], B = [[0], [50]]$$

Q2(c) [4 marks]

The balance is 50(90-θss) = 2.4525 sin θss. Solving gives a small error of about 0.05°.

Q2(d) [2 marks]

The gravity term changes the equilibrium, so the steady-state error is still nonzero. The poles should change.

Question 4 [10 marks]

Q4(a) [2 marks]

The characteristic polynomial is s^2+4s+8, so I report poles -4 and -8. Unity DC gain requires Nff=8.

Q4(b) [2 marks]

$$\theta_{ss} = 0.75 \times 8/(6+2) = 0.75,$$

the percentage tracking error is 25%

Q4(c) [4 marks]

The characteristic polynomial is $s^3+(a+bk_2)s^2+(c+bk_1)s+bK_I$. I use the target $s^3+6s^2+12s+16$, giving $k_2=4$, $k_1=6$, K_I=16.

Q4(d) [2 marks]

Integral action gives zero steady-state error if stable. A practical problem is integrator windup.